

91-21-11

WIRE LIST

91-21-11
WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
EFFECTIVE PAGES			W0000 cont.			W0000 cont.		
	1 thru 25	Nov 12/2012	R	26	Nov 12/2012	R	53	Nov 12/2012
	26	BLANK	R	27	Nov 12/2012	R	54	Nov 12/2012
R W0000	1	Nov 12/2012	R	28	Nov 12/2012	R	55	Nov 12/2012
R	2	Nov 12/2012	R	29	Nov 12/2012	R	56	Nov 12/2012
R	3	Nov 12/2012	R	30	Nov 12/2012	R	57	Nov 12/2012
R	4	Nov 12/2012	R	31	Nov 12/2012	R	58	Nov 12/2012
R	5	Nov 12/2012	R	32	Nov 12/2012	R	59	Nov 12/2012
R	6	Nov 12/2012	R	33	Nov 12/2012	R	60	Nov 12/2012
R	7	Nov 12/2012	R	34	Nov 12/2012	R	61	Nov 12/2012
R	8	Nov 12/2012	R	35	Nov 12/2012	R	62	Nov 12/2012
R	9	Nov 12/2012	R	36	Nov 12/2012	R	63	Nov 12/2012
R	10	Nov 12/2012	R	37	Nov 12/2012	R	64	Nov 12/2012
R	11	Nov 12/2012	R	38	Nov 12/2012	R	65	Nov 12/2012
R	12	Nov 12/2012	R	39	Nov 12/2012	R	66	Nov 12/2012
R	13	Nov 12/2012	R	40	Nov 12/2012	R	67	Nov 12/2012
R	14	Nov 12/2012	R	41	Nov 12/2012	R	68	Nov 12/2012
R	15	Nov 12/2012	R	42	Nov 12/2012	R	69	Nov 12/2012
R	16	Nov 12/2012	R	43	Nov 12/2012	R	70	Nov 12/2012
R	17	Nov 12/2012	R	44	Nov 12/2012	R	71	Nov 12/2012
R	18	Nov 12/2012	R	45	Nov 12/2012	R W0010	1	Nov 12/2012
R	19	Nov 12/2012	R	46	Nov 12/2012	R	2	Nov 12/2012
R	20	Nov 12/2012	R	47	Nov 12/2012	R	3	Nov 12/2012
R	21	Nov 12/2012	R	48	Nov 12/2012	R	4	Nov 12/2012
R	22	Nov 12/2012	R	49	Nov 12/2012	R	5	Nov 12/2012
R	23	Nov 12/2012	R	50	Nov 12/2012	R	6	Nov 12/2012
R	24	Nov 12/2012	R	51	Nov 12/2012	R	7	Nov 12/2012
R	25	Nov 12/2012	R	52	Nov 12/2012	R	8	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 1
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

91-21-11 WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
W0010 cont.			W0040 cont.			W0040 cont.		
R	9	Nov 12/2012	R	5	Nov 12/2012	R	32	Nov 12/2012
R	10	Nov 12/2012	R	6	Nov 12/2012	R	33	Nov 12/2012
R	11	Nov 12/2012	R	7	Nov 12/2012	R	34	Nov 12/2012
R	12	Nov 12/2012	R	8	Nov 12/2012	R	35	Nov 12/2012
R	13	Nov 12/2012	R	9	Nov 12/2012	R	36	Nov 12/2012
R W0020	1	Nov 12/2012	R	10	Nov 12/2012	R	37	Nov 12/2012
R	2	Nov 12/2012	R	11	Nov 12/2012	R	38	Nov 12/2012
R	3	Nov 12/2012	R	12	Nov 12/2012	R	39	Nov 12/2012
R	4	Nov 12/2012	R	13	Nov 12/2012	R	40	Nov 12/2012
R	5	Nov 12/2012	R	14	Nov 12/2012	R	41	Nov 12/2012
R	6	Nov 12/2012	R	15	Nov 12/2012	R	42	Nov 12/2012
R	7	Nov 12/2012	R	16	Nov 12/2012	R	43	Nov 12/2012
R	8	Nov 12/2012	R	17	Nov 12/2012	R	44	Nov 12/2012
R	9	Nov 12/2012	R	18	Nov 12/2012	R	45	Nov 12/2012
R	10	Nov 12/2012	R	19	Nov 12/2012	R	46	Nov 12/2012
R	11	Nov 12/2012	R	20	Nov 12/2012	R	47	Nov 12/2012
R	12	Nov 12/2012	R	21	Nov 12/2012	R	48	Nov 12/2012
R	13	Nov 12/2012	R	22	Nov 12/2012	R	49	Nov 12/2012
R	14	Nov 12/2012	R	23	Nov 12/2012	R	50	Nov 12/2012
R	15	Nov 12/2012	R	24	Nov 12/2012	R	51	Nov 12/2012
R	16	Nov 12/2012	R	25	Nov 12/2012	R	52	Nov 12/2012
R	17	Nov 12/2012	R	26	Nov 12/2012	R	53	Nov 12/2012
R	18	Nov 12/2012	R	27	Nov 12/2012	R	54	Nov 12/2012
R W0040	1	Nov 12/2012	R	28	Nov 12/2012	R	55	Nov 12/2012
R	2	Nov 12/2012	R	29	Nov 12/2012	R	56	Nov 12/2012
R	3	Nov 12/2012	R	30	Nov 12/2012	R	57	Nov 12/2012
R	4	Nov 12/2012	R	31	Nov 12/2012	R	58	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 2
Nov 12/2012

91-21-11
WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
W0040 cont.			W0070 cont.			W0080 cont.		
R	59	Nov 12/2012	R	5	Nov 12/2012	R	3	Nov 12/2012
R	60	Nov 12/2012	R	6	Nov 12/2012	R	4	Nov 12/2012
R	61	Nov 12/2012	R	7	Nov 12/2012	R	5	Nov 12/2012
R	62	Nov 12/2012	R	8	Nov 12/2012	R	6	Nov 12/2012
R	63	Nov 12/2012	R	9	Nov 12/2012	R	7	Nov 12/2012
R	64	Nov 12/2012	R	10	Nov 12/2012	R	8	Nov 12/2012
R	65	Nov 12/2012	R	11	Nov 12/2012	R	9	Nov 12/2012
R	66	Nov 12/2012	R	12	Nov 12/2012	R	10	Nov 12/2012
A	67	Nov 12/2012	R	13	Nov 12/2012	R	11	Nov 12/2012
R W0050	1	Nov 12/2012	R	14	Nov 12/2012	R	12	Nov 12/2012
R	2	Nov 12/2012	R	15	Nov 12/2012	R	13	Nov 12/2012
R	3	Nov 12/2012	R	16	Nov 12/2012	R	14	Nov 12/2012
R W0060	1	Nov 12/2012	R	17	Nov 12/2012	R	15	Nov 12/2012
R	2	Nov 12/2012	R	18	Nov 12/2012	R	16	Nov 12/2012
R	3	Nov 12/2012	R	19	Nov 12/2012	R	17	Nov 12/2012
R	4	Nov 12/2012	R	20	Nov 12/2012	R	18	Nov 12/2012
R	5	Nov 12/2012	R	21	Nov 12/2012	R	19	Nov 12/2012
R	6	Nov 12/2012	R	22	Nov 12/2012	R	20	Nov 12/2012
R	7	Nov 12/2012	R	23	Nov 12/2012	R	21	Nov 12/2012
R	8	Nov 12/2012	R	24	Nov 12/2012	R	22	Nov 12/2012
R	9	Nov 12/2012	R	25	Nov 12/2012	R	23	Nov 12/2012
R	10	Nov 12/2012	R	26	Nov 12/2012	R	24	Nov 12/2012
R	11	Nov 12/2012	R	27	Nov 12/2012	R	25	Nov 12/2012
R W0070	1	Nov 12/2012	R	28	Nov 12/2012	R	26	Nov 12/2012
R	2	Nov 12/2012	R	29	Nov 12/2012	R W0090	1	Nov 12/2012
R	3	Nov 12/2012	R W0080	1	Nov 12/2012	R	2	Nov 12/2012
R	4	Nov 12/2012	R	2	Nov 12/2012	R	3	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 3
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

91-21-11 WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
R W0100	1	Nov 12/2012	W0110 cont.			W0120 cont.		
R	2	Nov 12/2012	R	27	Nov 12/2012	R	8	Nov 12/2012
R W0110	1	Nov 12/2012	R	28	Nov 12/2012	R	9	Nov 12/2012
R	2	Nov 12/2012	R	29	Nov 12/2012	R	10	Nov 12/2012
R	3	Nov 12/2012	R	30	Nov 12/2012	R	11	Nov 12/2012
R	4	Nov 12/2012	R	31	Nov 12/2012	R	12	Nov 12/2012
R	5	Nov 12/2012	R	32	Nov 12/2012	R	13	Nov 12/2012
R	6	Nov 12/2012	R	33	Nov 12/2012	R	14	Nov 12/2012
R	7	Nov 12/2012	R	34	Nov 12/2012	R	15	Nov 12/2012
R	8	Nov 12/2012	R	35	Nov 12/2012	R W0130	1	Nov 12/2012
R	9	Nov 12/2012	R	36	Nov 12/2012	R	2	Nov 12/2012
R	10	Nov 12/2012	R	37	Nov 12/2012	R	3	Nov 12/2012
R	11	Nov 12/2012	R	38	Nov 12/2012	R	4	Nov 12/2012
R	12	Nov 12/2012	R	39	Nov 12/2012	R	5	Nov 12/2012
R	13	Nov 12/2012	R	40	Nov 12/2012	R	6	Nov 12/2012
R	14	Nov 12/2012	R	41	Nov 12/2012	R	7	Nov 12/2012
R	15	Nov 12/2012	R	42	Nov 12/2012	R	8	Nov 12/2012
R	16	Nov 12/2012	R	43	Nov 12/2012	R	9	Nov 12/2012
R	17	Nov 12/2012	R	44	Nov 12/2012	R	10	Nov 12/2012
R	18	Nov 12/2012	R	45	Nov 12/2012	R	11	Nov 12/2012
R	19	Nov 12/2012	R	46	Nov 12/2012	R	12	Nov 12/2012
R	20	Nov 12/2012	R W0120	1	Nov 12/2012	R	13	Nov 12/2012
R	21	Nov 12/2012	R	2	Nov 12/2012	R W0140	1	Nov 12/2012
R	22	Nov 12/2012	R	3	Nov 12/2012	R	2	Nov 12/2012
R	23	Nov 12/2012	R	4	Nov 12/2012	R	3	Nov 12/2012
R	24	Nov 12/2012	R	5	Nov 12/2012	R	4	Nov 12/2012
R	25	Nov 12/2012	R	6	Nov 12/2012	R	5	Nov 12/2012
R	26	Nov 12/2012	R	7	Nov 12/2012	R	6	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 4
Nov 12/2012

91-21-11
WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
W0140 cont.			R W0200	1	Nov 12/2012	W0220 cont.		
R	7	Nov 12/2012	R	2	Nov 12/2012	R	20	Nov 12/2012
R	8	Nov 12/2012	R W0210	1	Nov 12/2012	R	21	Nov 12/2012
R	9	Nov 12/2012	R	2	Nov 12/2012	R	22	Nov 12/2012
R	10	Nov 12/2012	R	3	Nov 12/2012	R	23	Nov 12/2012
R	11	Nov 12/2012	R	4	Nov 12/2012	R	24	Nov 12/2012
R	12	Nov 12/2012	R	5	Nov 12/2012	R	25	Nov 12/2012
R	13	Nov 12/2012	R	6	Nov 12/2012	R	26	Nov 12/2012
R	14	Nov 12/2012	R	7	Nov 12/2012	A	27	Nov 12/2012
R	15	Nov 12/2012	R W0220	1	Nov 12/2012	R W0310	1	Nov 12/2012
R	16	Nov 12/2012	R	2	Nov 12/2012	R	2	Nov 12/2012
R	17	Nov 12/2012	R	3	Nov 12/2012	R	3	Nov 12/2012
R	18	Nov 12/2012	R	4	Nov 12/2012	R	4	Nov 12/2012
R	19	Nov 12/2012	R	5	Nov 12/2012	R	5	Nov 12/2012
R	20	Nov 12/2012	R	6	Nov 12/2012	R	6	Nov 12/2012
R	21	Nov 12/2012	R	7	Nov 12/2012	R	7	Nov 12/2012
R	22	Nov 12/2012	R	8	Nov 12/2012	R	8	Nov 12/2012
R W0150	1	Nov 12/2012	R	9	Nov 12/2012	R	9	Nov 12/2012
R	2	Nov 12/2012	R	10	Nov 12/2012	R	10	Nov 12/2012
R	3	Nov 12/2012	R	11	Nov 12/2012	R	11	Nov 12/2012
R	4	Nov 12/2012	R	12	Nov 12/2012	R	12	Nov 12/2012
R	5	Nov 12/2012	R	13	Nov 12/2012	R	13	Nov 12/2012
R	6	Nov 12/2012	R	14	Nov 12/2012	R	14	Nov 12/2012
R	7	Nov 12/2012	R	15	Nov 12/2012	R	15	Nov 12/2012
R	8	Nov 12/2012	R	16	Nov 12/2012	R	16	Nov 12/2012
R	9	Nov 12/2012	R	17	Nov 12/2012	R	17	Nov 12/2012
R	10	Nov 12/2012	R	18	Nov 12/2012	R	18	Nov 12/2012
R W0160	1	Nov 12/2012	R	19	Nov 12/2012	R	19	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 5
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

91-21-11 WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
W0310 cont.			W0320 cont.			R W0330	1	Nov 12/2012
R	20	Nov 12/2012	R	12	Nov 12/2012	R	2	Nov 12/2012
R	21	Nov 12/2012	R	13	Nov 12/2012	R	3	Nov 12/2012
R	22	Nov 12/2012	R	14	Nov 12/2012	R	4	Nov 12/2012
R	23	Nov 12/2012	R	15	Nov 12/2012	R	5	Nov 12/2012
R	24	Nov 12/2012	R	16	Nov 12/2012	R	6	Nov 12/2012
R	25	Nov 12/2012	R	17	Nov 12/2012	R	7	Nov 12/2012
R	26	Nov 12/2012	R	18	Nov 12/2012	R	8	Nov 12/2012
R	27	Nov 12/2012	R	19	Nov 12/2012	R	9	Nov 12/2012
R	28	Nov 12/2012	R	20	Nov 12/2012	R	10	Nov 12/2012
R	29	Nov 12/2012	R	21	Nov 12/2012	R	11	Nov 12/2012
R	30	Nov 12/2012	R	22	Nov 12/2012	R	12	Nov 12/2012
R	31	Nov 12/2012	R	23	Nov 12/2012	R	13	Nov 12/2012
R	32	Nov 12/2012	R	24	Nov 12/2012	R	14	Nov 12/2012
R	33	Nov 12/2012	R	25	Nov 12/2012	R	15	Nov 12/2012
R	34	Nov 12/2012	R	26	Nov 12/2012	R	16	Nov 12/2012
R	35	Nov 12/2012	R	27	Nov 12/2012	R	17	Nov 12/2012
R W0320	1	Nov 12/2012	R	28	Nov 12/2012	R	18	Nov 12/2012
R	2	Nov 12/2012	R	29	Nov 12/2012	R	19	Nov 12/2012
R	3	Nov 12/2012	R	30	Nov 12/2012	R	20	Nov 12/2012
R	4	Nov 12/2012		31	Dec 19/2011	R	21	Nov 12/2012
R	5	Nov 12/2012	R	32	Nov 12/2012	R	22	Nov 12/2012
R	6	Nov 12/2012	R	33	Nov 12/2012	R	23	Nov 12/2012
R	7	Nov 12/2012	R	34	Nov 12/2012	R	24	Nov 12/2012
R	8	Nov 12/2012	R	35	Nov 12/2012	R	25	Nov 12/2012
R	9	Nov 12/2012	R	36	Nov 12/2012	R	26	Nov 12/2012
R	10	Nov 12/2012	R	37	Nov 12/2012	R	27	Nov 12/2012
R	11	Nov 12/2012		38	Dec 19/2011	R	28	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 6
Nov 12/2012

91-21-11
WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
W0330 cont.			W0410 cont.			W0410 cont.		
R	29	Nov 12/2012	R	18	Nov 12/2012	R	45	Nov 12/2012
R	30	Nov 12/2012	R	19	Nov 12/2012	R	46	Nov 12/2012
R	31	Nov 12/2012	R	20	Nov 12/2012	R	47	Nov 12/2012
A	32	Nov 12/2012	R	21	Nov 12/2012	R	48	Nov 12/2012
A	33	Nov 12/2012	R	22	Nov 12/2012	R	49	Nov 12/2012
A	34	Nov 12/2012	R	23	Nov 12/2012	R	50	Nov 12/2012
A	35	Nov 12/2012	R	24	Nov 12/2012	R	51	Nov 12/2012
A	36	Nov 12/2012	R	25	Nov 12/2012	O	52	Nov 12/2012
R W0340	1	Nov 12/2012	R	26	Nov 12/2012	R	53	Nov 12/2012
R W0350	1	Nov 12/2012	R	27	Nov 12/2012	R	54	Nov 12/2012
R W0410	1	Nov 12/2012	R	28	Nov 12/2012	R	55	Nov 12/2012
R	2	Nov 12/2012	R	29	Nov 12/2012	R	56	Nov 12/2012
R	3	Nov 12/2012	R	30	Nov 12/2012	R	57	Nov 12/2012
R	4	Nov 12/2012	R	31	Nov 12/2012	A	58	Nov 12/2012
R	5	Nov 12/2012	R	32	Nov 12/2012	R W0420	1	Nov 12/2012
R	6	Nov 12/2012	R	33	Nov 12/2012	R	2	Nov 12/2012
O	7	Nov 12/2012	R	34	Nov 12/2012	R	3	Nov 12/2012
R	8	Nov 12/2012	R	35	Nov 12/2012	R	4	Nov 12/2012
R	9	Nov 12/2012	R	36	Nov 12/2012	R	5	Nov 12/2012
R	10	Nov 12/2012	R	37	Nov 12/2012	R	6	Nov 12/2012
R	11	Nov 12/2012	R	38	Nov 12/2012	R	7	Nov 12/2012
R	12	Nov 12/2012	R	39	Nov 12/2012	R	8	Nov 12/2012
R	13	Nov 12/2012	R	40	Nov 12/2012	R	9	Nov 12/2012
R	14	Nov 12/2012	R	41	Nov 12/2012	R	10	Nov 12/2012
R	15	Nov 12/2012	R	42	Nov 12/2012	R	11	Nov 12/2012
R	16	Nov 12/2012	R	43	Nov 12/2012	R	12	Nov 12/2012
R	17	Nov 12/2012	R	44	Nov 12/2012	R	13	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 7
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

91-21-11 WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
R W0440	1	Nov 12/2012	W0520 cont.			W0610 cont.		
R	2	Nov 12/2012	R	25	Nov 12/2012	R	6	Nov 12/2012
R	3	Nov 12/2012	R	26	Nov 12/2012	R W0620	1	Nov 12/2012
R W0450	1	Nov 12/2012	R	27	Nov 12/2012	R	2	Nov 12/2012
R W0520	1	Nov 12/2012	R	28	Nov 12/2012	R	3	Nov 12/2012
R	2	Nov 12/2012	R	29	Nov 12/2012	R W0730	1	Nov 12/2012
R	3	Nov 12/2012	R	30	Nov 12/2012	R	2	Nov 12/2012
R	4	Nov 12/2012	R	31	Nov 12/2012	R W0760	1	Nov 12/2012
R	5	Nov 12/2012	R	32	Nov 12/2012	R W0810	1	Nov 12/2012
R	6	Nov 12/2012	R	33	Nov 12/2012	R	2	Nov 12/2012
R	7	Nov 12/2012	R	34	Nov 12/2012	R	3	Nov 12/2012
R	8	Nov 12/2012	R	35	Nov 12/2012	R	4	Nov 12/2012
R	9	Nov 12/2012	R	36	Nov 12/2012	R	5	Nov 12/2012
R	10	Nov 12/2012	R	37	Nov 12/2012	R	6	Nov 12/2012
R	11	Nov 12/2012	R	38	Nov 12/2012	R	7	Nov 12/2012
R	12	Nov 12/2012	R	39	Nov 12/2012	R	8	Nov 12/2012
R	13	Nov 12/2012	R	40	Nov 12/2012	R	9	Nov 12/2012
R	14	Nov 12/2012	R	41	Nov 12/2012	R	10	Nov 12/2012
R	15	Nov 12/2012	R	42	Nov 12/2012	R	11	Nov 12/2012
R	16	Nov 12/2012	R	43	Nov 12/2012	R	12	Nov 12/2012
R	17	Nov 12/2012	R	44	Nov 12/2012	R	13	Nov 12/2012
R	18	Nov 12/2012	R	45	Nov 12/2012	R	14	Nov 12/2012
R	19	Nov 12/2012	R	46	Nov 12/2012	R	15	Nov 12/2012
R	20	Nov 12/2012	R W0610	1	Nov 12/2012	R	16	Nov 12/2012
R	21	Nov 12/2012	R	2	Nov 12/2012	R	17	Nov 12/2012
R	22	Nov 12/2012	R	3	Nov 12/2012	R	18	Nov 12/2012
R	23	Nov 12/2012	R	4	Nov 12/2012	R	19	Nov 12/2012
R	24	Nov 12/2012	R	5	Nov 12/2012	R	20	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 8
Nov 12/2012

91-21-11
WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
R W1020	1	Nov 12/2012	W1030 cont.			W1170 cont.		
R	2	Nov 12/2012	R	12	Nov 12/2012	R	5	Nov 12/2012
R	3	Nov 12/2012	R	13	Nov 12/2012	R	6	Nov 12/2012
R	4	Nov 12/2012	R	14	Nov 12/2012	R	7	Nov 12/2012
R	5	Nov 12/2012	R	15	Nov 12/2012	R W1180	1	Nov 12/2012
R	6	Nov 12/2012	R	16	Nov 12/2012	R	2	Nov 12/2012
R	7	Nov 12/2012	R W1060	1	Nov 12/2012	R	3	Nov 12/2012
R	8	Nov 12/2012	R W1080	1	Nov 12/2012	R	4	Nov 12/2012
R	9	Nov 12/2012	R	2	Nov 12/2012	R	5	Nov 12/2012
R	10	Nov 12/2012	R	3	Nov 12/2012	R	6	Nov 12/2012
R	11	Nov 12/2012	R W1120	1	Nov 12/2012	R	7	Nov 12/2012
R	12	Nov 12/2012	R	2	Nov 12/2012	R	8	Nov 12/2012
R	13	Nov 12/2012	R	3	Nov 12/2012	R W1240	1	Nov 12/2012
R	14	Nov 12/2012	R W1130	1	Nov 12/2012	R W1260	1	Nov 12/2012
R	15	Nov 12/2012	R	2	Nov 12/2012	R	2	Nov 12/2012
R	16	Nov 12/2012	R W1140	1	Nov 12/2012	R	3	Nov 12/2012
R	17	Nov 12/2012	R W1160	1	Nov 12/2012	R	4	Nov 12/2012
R W1030	1	Nov 12/2012	R	2	Nov 12/2012	R	5	Nov 12/2012
R	2	Nov 12/2012	R	3	Nov 12/2012	R	6	Nov 12/2012
R	3	Nov 12/2012	R	4	Nov 12/2012	R	7	Nov 12/2012
R	4	Nov 12/2012	R	5	Nov 12/2012	R W1270	1	Nov 12/2012
R	5	Nov 12/2012	R	6	Nov 12/2012	R	2	Nov 12/2012
R	6	Nov 12/2012	R	7	Nov 12/2012	R	3	Nov 12/2012
R	7	Nov 12/2012	R	8	Nov 12/2012	R	4	Nov 12/2012
R	8	Nov 12/2012	R W1170	1	Nov 12/2012	R	5	Nov 12/2012
R	9	Nov 12/2012	R	2	Nov 12/2012	R	6	Nov 12/2012
R	10	Nov 12/2012	R	3	Nov 12/2012	R W1280	1	Nov 12/2012
R	11	Nov 12/2012	R	4	Nov 12/2012	R	2	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 9
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

91-21-11 WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
W1280 cont.			W2100 cont.			R W2130	1	Nov 12/2012
R	3	Nov 12/2012	R	6	Nov 12/2012	R	2	Nov 12/2012
R	4	Nov 12/2012	R	7	Nov 12/2012	R	3	Nov 12/2012
R	5	Nov 12/2012	R	8	Nov 12/2012	R	4	Nov 12/2012
R	6	Nov 12/2012	R	9	Nov 12/2012	R	5	Nov 12/2012
R	7	Nov 12/2012	R	10	Nov 12/2012	R	6	Nov 12/2012
R	8	Nov 12/2012	R	11	Nov 12/2012	R W2140	1	Nov 12/2012
R W1660	1	Nov 12/2012	A	12	Nov 12/2012	R	2	Nov 12/2012
R	2	Nov 12/2012	R W2110	1	Nov 12/2012	R	3	Nov 12/2012
R	3	Nov 12/2012	R	2	Nov 12/2012	R W2150	1	Nov 12/2012
R	4	Nov 12/2012	R	3	Nov 12/2012	R	2	Nov 12/2012
R	5	Nov 12/2012	R	4	Nov 12/2012	R	3	Nov 12/2012
R	6	Nov 12/2012	R	5	Nov 12/2012	R W2160	1	Nov 12/2012
R	7	Nov 12/2012	R	6	Nov 12/2012	R W2170	1	Nov 12/2012
R W2000	1	Nov 12/2012	R	7	Nov 12/2012	R	2	Nov 12/2012
R W2010	1	Nov 12/2012	R	8	Nov 12/2012	R	3	Nov 12/2012
R W2020	1	Nov 12/2012	R	9	Nov 12/2012	R W2200	1	Nov 12/2012
R W2030	1	Nov 12/2012	R	10	Nov 12/2012	R	2	Nov 12/2012
R	2	Nov 12/2012	R	11	Nov 12/2012	R	3	Nov 12/2012
R	3	Nov 12/2012	R	12	Nov 12/2012	R	4	Nov 12/2012
R	4	Nov 12/2012	R	13	Nov 12/2012	R	5	Nov 12/2012
R	5	Nov 12/2012	R	14	Nov 12/2012	R	6	Nov 12/2012
R	6	Nov 12/2012	R	15	Nov 12/2012	R	7	Nov 12/2012
R W2100	1	Nov 12/2012	R	16	Nov 12/2012	R	8	Nov 12/2012
R	2	Nov 12/2012	R	17	Nov 12/2012	R	9	Nov 12/2012
R	3	Nov 12/2012	R	18	Nov 12/2012	R	10	Nov 12/2012
R	4	Nov 12/2012	R	19	Nov 12/2012	R	11	Nov 12/2012
R	5	Nov 12/2012	R	20	Nov 12/2012	R W2210	1	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 10
Nov 12/2012

91-21-11
WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
W2210 cont.			W2210 cont.			R W2300	1	Nov 12/2012
R	2	Nov 12/2012	R	29	Nov 12/2012	R W2360	1	Nov 12/2012
R	3	Nov 12/2012	R	30	Nov 12/2012	R	2	Nov 12/2012
R	4	Nov 12/2012	R	31	Nov 12/2012	R W2380	1	Nov 12/2012
R	5	Nov 12/2012	R	32	Nov 12/2012	R	2	Nov 12/2012
R	6	Nov 12/2012	R	33	Nov 12/2012	R W2400	1	Nov 12/2012
R	7	Nov 12/2012	R	34	Nov 12/2012	R	2	Nov 12/2012
R	8	Nov 12/2012	R	35	Nov 12/2012	R W2410	1	Nov 12/2012
R	9	Nov 12/2012	R	36	Nov 12/2012	R	2	Nov 12/2012
R	10	Nov 12/2012	R	37	Nov 12/2012	R	3	Nov 12/2012
R	11	Nov 12/2012	R	38	Nov 12/2012	R	4	Nov 12/2012
R	12	Nov 12/2012	R	39	Nov 12/2012	R	5	Nov 12/2012
R	13	Nov 12/2012	R	40	Nov 12/2012	R W2460	1	Nov 12/2012
R	14	Nov 12/2012	R	41	Nov 12/2012	R	2	Nov 12/2012
R	15	Nov 12/2012	A	42	Nov 12/2012	R W2500	1	Nov 12/2012
R	16	Nov 12/2012	A	43	Nov 12/2012	R	2	Nov 12/2012
R	17	Nov 12/2012	A	44	Nov 12/2012	R	3	Nov 12/2012
R	18	Nov 12/2012	R W2220	1	Nov 12/2012	R	4	Nov 12/2012
R	19	Nov 12/2012	R	2	Nov 12/2012	R	5	Nov 12/2012
R	20	Nov 12/2012	R W2230	1	Nov 12/2012	R	6	Nov 12/2012
R	21	Nov 12/2012	R	2	Nov 12/2012	R	7	Nov 12/2012
R	22	Nov 12/2012	R	3	Nov 12/2012	R	8	Nov 12/2012
R	23	Nov 12/2012	R	4	Nov 12/2012	R	9	Nov 12/2012
R	24	Nov 12/2012	R W2240	1	Nov 12/2012	R	10	Nov 12/2012
R	25	Nov 12/2012	R	2	Nov 12/2012	R	11	Nov 12/2012
R	26	Nov 12/2012	R W2250	1	Nov 12/2012	R	12	Nov 12/2012
R	27	Nov 12/2012	R W2260	1	Nov 12/2012	R	13	Nov 12/2012
R	28	Nov 12/2012	R	2	Nov 12/2012	R	14	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 11
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

91-21-11 WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
W2500 cont.			W2510 cont.			R W3010	1	Nov 12/2012
R	15	Nov 12/2012	R	7	Nov 12/2012	R	2	Nov 12/2012
R	16	Nov 12/2012	R W2520	1	Nov 12/2012	R	3	Nov 12/2012
R	17	Nov 12/2012	R W2530	1	Nov 12/2012	R W3020	1	Nov 12/2012
R	18	Nov 12/2012	R	2	Nov 12/2012	R	2	Nov 12/2012
R	19	Nov 12/2012	R	3	Nov 12/2012	R	3	Nov 12/2012
R	20	Nov 12/2012	R W2580	1	Nov 12/2012	R W3030	1	Nov 12/2012
R	21	Nov 12/2012	R	2	Nov 12/2012	R	2	Nov 12/2012
R	22	Nov 12/2012	R W2590	1	Nov 12/2012		3	Aug 14/2012
R	23	Nov 12/2012	R	2	Nov 12/2012	R W3040	1	Nov 12/2012
R	24	Nov 12/2012	R	3	Nov 12/2012	R	2	Nov 12/2012
R	25	Nov 12/2012	R	4	Nov 12/2012	R	3	Nov 12/2012
R	26	Nov 12/2012		5	Aug 14/2012	R W3050	1	Nov 12/2012
R	27	Nov 12/2012	R W2650	1	Nov 12/2012	R	2	Nov 12/2012
R	28	Nov 12/2012	R	2	Nov 12/2012	R	3	Nov 12/2012
R	29	Nov 12/2012	R W2660	1	Nov 12/2012	R	4	Nov 12/2012
R	30	Nov 12/2012	R W2700	1	Nov 12/2012	R	5	Nov 12/2012
R	31	Nov 12/2012	W2730	1	Aug 14/2012	R	6	Nov 12/2012
R	32	Nov 12/2012	R W2800	1	Nov 12/2012	R	7	Nov 12/2012
R	33	Nov 12/2012	R	2	Nov 12/2012	R	8	Nov 12/2012
R	34	Nov 12/2012	R	3	Nov 12/2012	R	9	Nov 12/2012
R	35	Nov 12/2012	R W2870	1	Nov 12/2012	R	10	Nov 12/2012
R W2510	1	Nov 12/2012	R W2880	1	Nov 12/2012	R	11	Nov 12/2012
R	2	Nov 12/2012	R	2	Nov 12/2012	R	12	Nov 12/2012
R	3	Nov 12/2012	R W3000	1	Nov 12/2012	R	13	Nov 12/2012
R	4	Nov 12/2012	R	2	Nov 12/2012	R	14	Nov 12/2012
R	5	Nov 12/2012	R	3	Nov 12/2012	R	15	Nov 12/2012
R	6	Nov 12/2012	R	4	Nov 12/2012	R	16	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 12
Nov 12/2012

91-21-11
WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
W3050 cont.			W3140 cont.			W3150 cont.		
R	17	Nov 12/2012	R	18	Nov 12/2012	R	14	Nov 12/2012
R W3060	1	Nov 12/2012	R	19	Nov 12/2012	R	15	Nov 12/2012
R	2	Nov 12/2012	R	20	Nov 12/2012	R	16	Nov 12/2012
R W3070	1	Nov 12/2012	R	21	Nov 12/2012	R	17	Nov 12/2012
R	2	Nov 12/2012	R	22	Nov 12/2012	R	18	Nov 12/2012
R W3090	1	Nov 12/2012	R	23	Nov 12/2012	R	19	Nov 12/2012
R W3100	1	Nov 12/2012	R	24	Nov 12/2012	R	20	Nov 12/2012
R	2	Nov 12/2012	R	25	Nov 12/2012	R	21	Nov 12/2012
W3130	1	Aug 14/2012	R	26	Nov 12/2012	R	22	Nov 12/2012
	2	Aug 14/2012	R	27	Nov 12/2012	R	23	Nov 12/2012
R W3140	1	Nov 12/2012	R	28	Nov 12/2012	R	24	Nov 12/2012
R	2	Nov 12/2012	R	29	Nov 12/2012	R	25	Nov 12/2012
R	3	Nov 12/2012	R	30	Nov 12/2012	R	26	Nov 12/2012
R	4	Nov 12/2012	R	31	Nov 12/2012	R	27	Nov 12/2012
R	5	Nov 12/2012	R W3150	1	Nov 12/2012	R	28	Nov 12/2012
R	6	Nov 12/2012	R	2	Nov 12/2012	R	29	Nov 12/2012
R	7	Nov 12/2012	R	3	Nov 12/2012	R	30	Nov 12/2012
R	8	Nov 12/2012	R	4	Nov 12/2012	R	31	Nov 12/2012
R	9	Nov 12/2012	R	5	Nov 12/2012	R	32	Nov 12/2012
R	10	Nov 12/2012	R	6	Nov 12/2012	R	33	Nov 12/2012
R	11	Nov 12/2012	R	7	Nov 12/2012	R	34	Nov 12/2012
R	12	Nov 12/2012	R	8	Nov 12/2012	R	35	Nov 12/2012
R	13	Nov 12/2012	R	9	Nov 12/2012	R	36	Nov 12/2012
R	14	Nov 12/2012	R	10	Nov 12/2012	R	37	Nov 12/2012
R	15	Nov 12/2012	R	11	Nov 12/2012	R	38	Nov 12/2012
R	16	Nov 12/2012	R	12	Nov 12/2012	R	39	Nov 12/2012
R	17	Nov 12/2012	R	13	Nov 12/2012	R	40	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 13
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

91-21-11 WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
W3150 cont.			W3160 cont.			W3280 cont.		
R	41	Nov 12/2012	R	5	Nov 12/2012		3	Aug 14/2012
R	42	Nov 12/2012	R	6	Nov 12/2012	W3290	1	Aug 14/2012
R	43	Nov 12/2012	R	7	Nov 12/2012		2	Aug 14/2012
R	44	Nov 12/2012	R	8	Nov 12/2012	R W3300	1	Nov 12/2012
R	45	Nov 12/2012	R	9	Nov 12/2012	R	2	Nov 12/2012
R	46	Nov 12/2012	R	10	Nov 12/2012	R	3	Nov 12/2012
R	47	Nov 12/2012	R	11	Nov 12/2012	R	4	Nov 12/2012
R	48	Nov 12/2012	R W3170	1	Nov 12/2012	R	5	Nov 12/2012
R	49	Nov 12/2012	R	2	Nov 12/2012	R	6	Nov 12/2012
R	50	Nov 12/2012	W3190	1	Aug 14/2012	R W3310	1	Nov 12/2012
R	51	Nov 12/2012		2	Aug 14/2012	R	2	Nov 12/2012
R	52	Nov 12/2012		3	Aug 14/2012	R	3	Nov 12/2012
R	53	Nov 12/2012	W3200	1	Aug 14/2012	R	4	Nov 12/2012
R	54	Nov 12/2012	R W3240	1	Nov 12/2012	R	5	Nov 12/2012
R	55	Nov 12/2012	R	2	Nov 12/2012	R	6	Nov 12/2012
R	56	Nov 12/2012		3	Aug 14/2012	R W3320	1	Nov 12/2012
R	57	Nov 12/2012	W3250	1	Aug 14/2012	R	2	Nov 12/2012
R	58	Nov 12/2012		2	Aug 14/2012	R	3	Nov 12/2012
R	59	Nov 12/2012		3	Aug 14/2012	R	4	Nov 12/2012
R	60	Nov 12/2012	W3260	1	Aug 14/2012	R	5	Nov 12/2012
R	61	Nov 12/2012		2	Aug 14/2012	R	6	Nov 12/2012
R	62	Nov 12/2012		3	Aug 14/2012	R	7	Nov 12/2012
R	63	Nov 12/2012	W3270	1	Aug 14/2012	R	8	Nov 12/2012
R W3160	1	Nov 12/2012		2	Aug 14/2012	R	9	Nov 12/2012
R	2	Nov 12/2012		3	Aug 14/2012	R	10	Nov 12/2012
R	3	Nov 12/2012	W3280	1	Aug 14/2012	R W3330	1	Nov 12/2012
R	4	Nov 12/2012		2	Aug 14/2012	R	2	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 14
Nov 12/2012

91-21-11
WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date			
W3330 cont.			W3390 cont.			W3580 cont.					
R	3	Nov 12/2012	R	9	Nov 12/2012	R	9	Nov 12/2012			
W3340	1	Aug 14/2012	R	10	Nov 12/2012	R	W3590	1	Nov 12/2012		
	2	Aug 14/2012	R	11	Nov 12/2012	R		2	Nov 12/2012		
	3	Aug 14/2012	R	12	Nov 12/2012	R		3	Nov 12/2012		
R	W3370	1	Nov 12/2012	R	W3410	1	Nov 12/2012	R	4	Nov 12/2012	
R		2	Nov 12/2012	R		2	Nov 12/2012	R	5	Nov 12/2012	
R		3	Nov 12/2012	R		3	Nov 12/2012	R	6	Nov 12/2012	
R		4	Nov 12/2012	R		4	Nov 12/2012	R	7	Nov 12/2012	
R		5	Nov 12/2012	R	W3470	1	Nov 12/2012	R	8	Nov 12/2012	
R		6	Nov 12/2012	R		2	Nov 12/2012	R	9	Nov 12/2012	
R		7	Nov 12/2012	R		3	Nov 12/2012	R	10	Nov 12/2012	
R		8	Nov 12/2012	R	W3490	1	Nov 12/2012	R	11	Nov 12/2012	
R		9	Nov 12/2012	R		2	Nov 12/2012	R	12	Nov 12/2012	
R		10	Nov 12/2012	R	W3500	1	Nov 12/2012		W3600	1	Aug 14/2012
R	W3380	1	Nov 12/2012	R	W3510	1	Nov 12/2012			2	Aug 14/2012
R		2	Nov 12/2012		W3520	1	Aug 14/2012	R		3	Nov 12/2012
R		3	Nov 12/2012	R	W3550	1	Nov 12/2012	R		4	Nov 12/2012
R		4	Nov 12/2012	R	W3570	1	Nov 12/2012		W3650	1	Aug 14/2012
R		5	Nov 12/2012	R		2	Nov 12/2012			2	Aug 14/2012
R	W3390	1	Nov 12/2012	R	W3580	1	Nov 12/2012	R		3	Nov 12/2012
R		2	Nov 12/2012	R		2	Nov 12/2012	R		4	Nov 12/2012
R		3	Nov 12/2012	R		3	Nov 12/2012	R		5	Nov 12/2012
R		4	Nov 12/2012	R		4	Nov 12/2012	R		6	Nov 12/2012
R		5	Nov 12/2012	R		5	Nov 12/2012	R		7	Nov 12/2012
R		6	Nov 12/2012	R		6	Nov 12/2012	R	W3660	1	Nov 12/2012
R		7	Nov 12/2012			7	Aug 14/2012	R		2	Nov 12/2012
R		8	Nov 12/2012	R		8	Nov 12/2012	R		3	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 15
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

91-21-11 WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
R W3670	1	Nov 12/2012	W4140 cont.			W4160 cont.		
R	2	Nov 12/2012	R	9	Nov 12/2012	R	11	Nov 12/2012
R	3	Nov 12/2012	R	10	Nov 12/2012	A	12	Nov 12/2012
R W3690	1	Nov 12/2012	R	11	Nov 12/2012	R W4170	1	Nov 12/2012
R W3700	1	Nov 12/2012	R	12	Nov 12/2012	R W4180	1	Nov 12/2012
R	2	Nov 12/2012	R	13	Nov 12/2012	O W4190	1	Nov 12/2012
R	3	Nov 12/2012	R	14	Nov 12/2012	O	2	Nov 12/2012
R W3710	1	Nov 12/2012	R	15	Nov 12/2012	O	3	Nov 12/2012
R W3800	1	Nov 12/2012	R	16	Nov 12/2012	O	4	Nov 12/2012
R	2	Nov 12/2012	R	17	Nov 12/2012	R W4220	1	Nov 12/2012
R	3	Nov 12/2012	R	18	Nov 12/2012	R	2	Nov 12/2012
R	4	Nov 12/2012	R	19	Nov 12/2012	R	3	Nov 12/2012
R W3890	1	Nov 12/2012	R	20	Nov 12/2012	R W4240	1	Nov 12/2012
R W3900	1	Nov 12/2012	R	21	Nov 12/2012	R	2	Nov 12/2012
R W4000	1	Nov 12/2012	R	22	Nov 12/2012	R	3	Nov 12/2012
R W4110	1	Nov 12/2012	R	23	Nov 12/2012	R	4	Nov 12/2012
R W4130	1	Nov 12/2012	R	24	Nov 12/2012	R	5	Nov 12/2012
R	2	Nov 12/2012	R	25	Nov 12/2012	R W4250	1	Nov 12/2012
R	3	Nov 12/2012	R W4160	1	Nov 12/2012	R	2	Nov 12/2012
R	4	Nov 12/2012	R	2	Nov 12/2012	R	3	Nov 12/2012
R W4140	1	Nov 12/2012	R	3	Nov 12/2012	R	4	Nov 12/2012
R	2	Nov 12/2012	R	4	Nov 12/2012	R	5	Nov 12/2012
R	3	Nov 12/2012	R	5	Nov 12/2012	R	6	Nov 12/2012
R	4	Nov 12/2012	R	6	Nov 12/2012	R	7	Nov 12/2012
R	5	Nov 12/2012	R	7	Nov 12/2012	R	8	Nov 12/2012
R	6	Nov 12/2012	R	8	Nov 12/2012	R	9	Nov 12/2012
R	7	Nov 12/2012	R	9	Nov 12/2012	R	10	Nov 12/2012
R	8	Nov 12/2012	R	10	Nov 12/2012	R	11	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 16
Nov 12/2012

91-21-11
WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
W4250 cont.			W4250 cont.			W4720 cont.		
R	12	Nov 12/2012	R	39	Nov 12/2012	R	5	Nov 12/2012
R	13	Nov 12/2012	R	40	Nov 12/2012	R	6	Nov 12/2012
R	14	Nov 12/2012	R	41	Nov 12/2012	R	7	Nov 12/2012
R	15	Nov 12/2012	R	42	Nov 12/2012	R	8	Nov 12/2012
R	16	Nov 12/2012	R	43	Nov 12/2012	R	9	Nov 12/2012
R	17	Nov 12/2012	R	44	Nov 12/2012	R	10	Nov 12/2012
R	18	Nov 12/2012	R	45	Nov 12/2012	R	11	Nov 12/2012
R	19	Nov 12/2012	R	46	Nov 12/2012	R	12	Nov 12/2012
R	20	Nov 12/2012	R	47	Nov 12/2012	R	13	Nov 12/2012
R	21	Nov 12/2012	R	48	Nov 12/2012	R	14	Nov 12/2012
R	22	Nov 12/2012	R	49	Nov 12/2012	R	15	Nov 12/2012
R	23	Nov 12/2012	R	50	Nov 12/2012	R	16	Nov 12/2012
R	24	Nov 12/2012	R	51	Nov 12/2012	R W5000	1	Nov 12/2012
R	25	Nov 12/2012	R	52	Nov 12/2012	R W5020	1	Nov 12/2012
R	26	Nov 12/2012	R	53	Nov 12/2012	R W5030	1	Nov 12/2012
R	27	Nov 12/2012	R	54	Nov 12/2012	R	2	Nov 12/2012
R	28	Nov 12/2012	R	55	Nov 12/2012	R	3	Nov 12/2012
R	29	Nov 12/2012	R	56	Nov 12/2012	R W5040	1	Nov 12/2012
R	30	Nov 12/2012	R	57	Nov 12/2012	R W5050	1	Nov 12/2012
R	31	Nov 12/2012	R	58	Nov 12/2012	R W5070	1	Nov 12/2012
R	32	Nov 12/2012	R	59	Nov 12/2012	R	2	Nov 12/2012
R	33	Nov 12/2012	R	60	Nov 12/2012	R W5080	1	Nov 12/2012
R	34	Nov 12/2012	R	61	Nov 12/2012	R	2	Nov 12/2012
R	35	Nov 12/2012	R W4720	1	Nov 12/2012	R	3	Nov 12/2012
R	36	Nov 12/2012	R	2	Nov 12/2012	R	4	Nov 12/2012
R	37	Nov 12/2012	R	3	Nov 12/2012	R	5	Nov 12/2012
R	38	Nov 12/2012	R	4	Nov 12/2012	R W5090	1	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 17
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

91-21-11 WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
W5090 cont.			W5100 cont.			W5110 cont.		
R	2	Nov 12/2012	R	21	Nov 12/2012	R	24	Nov 12/2012
R	3	Nov 12/2012	R	22	Nov 12/2012	R	25	Nov 12/2012
R	4	Nov 12/2012	R	23	Nov 12/2012	R	26	Nov 12/2012
R	5	Nov 12/2012	A	24	Nov 12/2012	R	27	Nov 12/2012
R	6	Nov 12/2012	R W5110	1	Nov 12/2012	R	28	Nov 12/2012
R	7	Nov 12/2012	R	2	Nov 12/2012	R	29	Nov 12/2012
R	8	Nov 12/2012	R	3	Nov 12/2012	R	30	Nov 12/2012
R W5100	1	Nov 12/2012	R	4	Nov 12/2012	R W5120	1	Nov 12/2012
R	2	Nov 12/2012	R	5	Nov 12/2012	R	2	Nov 12/2012
R	3	Nov 12/2012	R	6	Nov 12/2012	R	3	Nov 12/2012
R	4	Nov 12/2012	R	7	Nov 12/2012	R	4	Nov 12/2012
R	5	Nov 12/2012	R	8	Nov 12/2012	R	5	Nov 12/2012
R	6	Nov 12/2012	R	9	Nov 12/2012	R	6	Nov 12/2012
R	7	Nov 12/2012	R	10	Nov 12/2012	R	7	Nov 12/2012
R	8	Nov 12/2012	R	11	Nov 12/2012	R	8	Nov 12/2012
R	9	Nov 12/2012	R	12	Nov 12/2012	R	9	Nov 12/2012
R	10	Nov 12/2012	R	13	Nov 12/2012	R	10	Nov 12/2012
R	11	Nov 12/2012	R	14	Nov 12/2012	R	11	Nov 12/2012
R	12	Nov 12/2012	R	15	Nov 12/2012	R	12	Nov 12/2012
R	13	Nov 12/2012	R	16	Nov 12/2012	R	13	Nov 12/2012
R	14	Nov 12/2012	R	17	Nov 12/2012	R	14	Nov 12/2012
R	15	Nov 12/2012	R	18	Nov 12/2012	R	15	Nov 12/2012
R	16	Nov 12/2012	R	19	Nov 12/2012	R	16	Nov 12/2012
R	17	Nov 12/2012	R	20	Nov 12/2012	R W5130	1	Nov 12/2012
R	18	Nov 12/2012	R	21	Nov 12/2012	R W5140	1	Nov 12/2012
R	19	Nov 12/2012	R	22	Nov 12/2012	R	2	Nov 12/2012
R	20	Nov 12/2012	R	23	Nov 12/2012	R	3	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 18
Nov 12/2012

91-21-11
WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
W5140 cont.			W5150 cont.			W5160 cont.		
R	4	Nov 12/2012	R	27	Nov 12/2012	R	26	Nov 12/2012
R W5150	1	Nov 12/2012	R	28	Nov 12/2012	R	27	Nov 12/2012
R	2	Nov 12/2012	R W5160	1	Nov 12/2012	R	28	Nov 12/2012
R	3	Nov 12/2012	R	2	Nov 12/2012	R	29	Nov 12/2012
R	4	Nov 12/2012	R	3	Nov 12/2012	R	30	Nov 12/2012
R	5	Nov 12/2012	R	4	Nov 12/2012	R	31	Nov 12/2012
R	6	Nov 12/2012	R	5	Nov 12/2012	R	32	Nov 12/2012
R	7	Nov 12/2012	R	6	Nov 12/2012	R	33	Nov 12/2012
R	8	Nov 12/2012	R	7	Nov 12/2012	R	34	Nov 12/2012
R	9	Nov 12/2012	R	8	Nov 12/2012	R W5170	1	Nov 12/2012
R	10	Nov 12/2012	R	9	Nov 12/2012	R	2	Nov 12/2012
R	11	Nov 12/2012	R	10	Nov 12/2012	R	3	Nov 12/2012
R	12	Nov 12/2012	R	11	Nov 12/2012	R	4	Nov 12/2012
R	13	Nov 12/2012	R	12	Nov 12/2012	R	5	Nov 12/2012
R	14	Nov 12/2012	R	13	Nov 12/2012	R	6	Nov 12/2012
R	15	Nov 12/2012	R	14	Nov 12/2012	R W5180	1	Nov 12/2012
R	16	Nov 12/2012	R	15	Nov 12/2012	R	2	Nov 12/2012
R	17	Nov 12/2012	R	16	Nov 12/2012	R	3	Nov 12/2012
R	18	Nov 12/2012	R	17	Nov 12/2012	R	4	Nov 12/2012
R	19	Nov 12/2012	R	18	Nov 12/2012	R	5	Nov 12/2012
R	20	Nov 12/2012	R	19	Nov 12/2012	R	6	Nov 12/2012
R	21	Nov 12/2012	R	20	Nov 12/2012	R	7	Nov 12/2012
R	22	Nov 12/2012	R	21	Nov 12/2012	R W5190	1	Nov 12/2012
R	23	Nov 12/2012	R	22	Nov 12/2012	R	2	Nov 12/2012
R	24	Nov 12/2012	R	23	Nov 12/2012	R	3	Nov 12/2012
R	25	Nov 12/2012	R	24	Nov 12/2012	R	4	Nov 12/2012
R	26	Nov 12/2012	R	25	Nov 12/2012	R W5200	1	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 19
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

91-21-11 WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
W5200 cont.			W5270 cont.			R W5360	1	Nov 12/2012
R	2	Nov 12/2012	R	2	Nov 12/2012	R	2	Nov 12/2012
R	3	Nov 12/2012	R W5290	1	Nov 12/2012	R	3	Nov 12/2012
R	4	Nov 12/2012	R W5300	1	Nov 12/2012	R	4	Nov 12/2012
R	5	Nov 12/2012	R	2	Nov 12/2012	R	5	Nov 12/2012
R	6	Nov 12/2012	R	3	Nov 12/2012	R	6	Nov 12/2012
R	7	Nov 12/2012	R	4	Nov 12/2012	R	7	Nov 12/2012
R	8	Nov 12/2012	R	5	Nov 12/2012	R	8	Nov 12/2012
R	9	Nov 12/2012	R	6	Nov 12/2012	R	9	Nov 12/2012
R	10	Nov 12/2012	R	7	Nov 12/2012	R W5370	1	Nov 12/2012
R	11	Nov 12/2012	R	8	Nov 12/2012	R	2	Nov 12/2012
R W5220	1	Nov 12/2012	R	9	Nov 12/2012	R	3	Nov 12/2012
R	2	Nov 12/2012	R W5310	1	Nov 12/2012	R	4	Nov 12/2012
R	3	Nov 12/2012	R	2	Nov 12/2012	R	5	Nov 12/2012
R	4	Nov 12/2012	R	3	Nov 12/2012	R	6	Nov 12/2012
R	5	Nov 12/2012	R W5330	1	Nov 12/2012	R W5380	1	Nov 12/2012
R W5230	1	Nov 12/2012	R	2	Nov 12/2012	R	2	Nov 12/2012
R	2	Nov 12/2012	R	3	Nov 12/2012	R	3	Nov 12/2012
R	3	Nov 12/2012	R	4	Nov 12/2012	R	4	Nov 12/2012
R	4	Nov 12/2012	R	5	Nov 12/2012	R	5	Nov 12/2012
R	5	Nov 12/2012	R	6	Nov 12/2012	R W5390	1	Nov 12/2012
A	6	Nov 12/2012	R	7	Nov 12/2012	R W5400	1	Nov 12/2012
R W5240	1	Nov 12/2012	R	8	Nov 12/2012	R W5410	1	Nov 12/2012
R	2	Nov 12/2012	R	9	Nov 12/2012	R W5430	1	Nov 12/2012
R	3	Nov 12/2012	R	10	Nov 12/2012	R	2	Nov 12/2012
R	4	Nov 12/2012	R	11	Nov 12/2012	R	3	Nov 12/2012
R W5250	1	Nov 12/2012	R W5350	1	Nov 12/2012	R	4	Nov 12/2012
R W5270	1	Nov 12/2012	R	2	Nov 12/2012	R	5	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 20
Nov 12/2012

91-21-11
WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
W5430 cont.			W5500 cont.			W5520 cont.		
R	6	Nov 12/2012	R	11	Nov 12/2012	R	2	Nov 12/2012
R W5450	1	Nov 12/2012	R	12	Nov 12/2012	R	3	Nov 12/2012
R	2	Nov 12/2012	R	13	Nov 12/2012	R	4	Nov 12/2012
R W5460	1	Nov 12/2012	R	14	Nov 12/2012	R	5	Nov 12/2012
R	2	Nov 12/2012	R	15	Nov 12/2012	R W5530	1	Nov 12/2012
R	3	Nov 12/2012	R	16	Nov 12/2012	R	2	Nov 12/2012
R	4	Nov 12/2012	R	17	Nov 12/2012	R W5560	1	Nov 12/2012
R	5	Nov 12/2012	R	18	Nov 12/2012	R	2	Nov 12/2012
R	6	Nov 12/2012	R	19	Nov 12/2012	R	3	Nov 12/2012
R	7	Nov 12/2012	R	20	Nov 12/2012	R	4	Nov 12/2012
R	8	Nov 12/2012	R	21	Nov 12/2012	R	5	Nov 12/2012
R	9	Nov 12/2012	R	22	Nov 12/2012	R W5580	1	Nov 12/2012
R	10	Nov 12/2012	R	23	Nov 12/2012	R	2	Nov 12/2012
R	11	Nov 12/2012	R	24	Nov 12/2012	R W5590	1	Nov 12/2012
R	12	Nov 12/2012	R	25	Nov 12/2012	R W5600	1	Nov 12/2012
R	13	Nov 12/2012	R W5510	1	Nov 12/2012	R	2	Nov 12/2012
R	14	Nov 12/2012	R	2	Nov 12/2012	R W5610	1	Nov 12/2012
R W5500	1	Nov 12/2012	R	3	Nov 12/2012	R	2	Nov 12/2012
R	2	Nov 12/2012	R	4	Nov 12/2012	R	3	Nov 12/2012
R	3	Nov 12/2012	R	5	Nov 12/2012	R	4	Nov 12/2012
R	4	Nov 12/2012	R	6	Nov 12/2012	R	5	Nov 12/2012
R	5	Nov 12/2012	R	7	Nov 12/2012	R	6	Nov 12/2012
R	6	Nov 12/2012	R	8	Nov 12/2012	R	7	Nov 12/2012
R	7	Nov 12/2012	R	9	Nov 12/2012	R W5710	1	Nov 12/2012
R	8	Nov 12/2012	R	10	Nov 12/2012	R	2	Nov 12/2012
R	9	Nov 12/2012	R	11	Nov 12/2012	R	3	Nov 12/2012
R	10	Nov 12/2012	R W5520	1	Nov 12/2012	R	4	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 21
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

91-21-11 WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
W5710 cont.			R W5830	1	Nov 12/2012	W6130 cont.		
R	5	Nov 12/2012	R W6020	1	Nov 12/2012	R	5	Nov 12/2012
R	6	Nov 12/2012	R	2	Nov 12/2012	R	6	Nov 12/2012
R	7	Nov 12/2012	R	3	Nov 12/2012	R	7	Nov 12/2012
R W5720	1	Nov 12/2012	R	4	Nov 12/2012	R	8	Nov 12/2012
R	2	Nov 12/2012	R W6030	1	Nov 12/2012	R	9	Nov 12/2012
R	3	Nov 12/2012	R	2	Nov 12/2012	R	10	Nov 12/2012
R	4	Nov 12/2012	R	3	Nov 12/2012	R	11	Nov 12/2012
R	5	Nov 12/2012	R W6100	1	Nov 12/2012	R	12	Nov 12/2012
R	6	Nov 12/2012	R	2	Nov 12/2012	R	13	Nov 12/2012
R	7	Nov 12/2012	R W6110	1	Nov 12/2012	R	14	Nov 12/2012
R	8	Nov 12/2012	R	2	Nov 12/2012	R W6160	1	Nov 12/2012
R	9	Nov 12/2012	R	3	Nov 12/2012	R	2	Nov 12/2012
R	10	Nov 12/2012	R	4	Nov 12/2012	R	3	Nov 12/2012
R	11	Nov 12/2012	R W6120	1	Nov 12/2012	R	4	Nov 12/2012
R	12	Nov 12/2012	R	2	Nov 12/2012	R	5	Nov 12/2012
R	13	Nov 12/2012	R	3	Nov 12/2012	R	6	Nov 12/2012
R	14	Nov 12/2012	R	4	Nov 12/2012	R	7	Nov 12/2012
R	15	Nov 12/2012	R	5	Nov 12/2012	R	8	Nov 12/2012
R	16	Nov 12/2012	R	6	Nov 12/2012	R W6170	1	Nov 12/2012
R	17	Nov 12/2012	R	7	Nov 12/2012	R	2	Nov 12/2012
R	18	Nov 12/2012	R	8	Nov 12/2012	R	3	Nov 12/2012
R	19	Nov 12/2012	R	9	Nov 12/2012	R	4	Nov 12/2012
R	20	Nov 12/2012	A	10	Nov 12/2012	R	5	Nov 12/2012
R	21	Nov 12/2012	R W6130	1	Nov 12/2012	R	6	Nov 12/2012
R	22	Nov 12/2012	R	2	Nov 12/2012	R	7	Nov 12/2012
R	23	Nov 12/2012	R	3	Nov 12/2012	R W6180	1	Nov 12/2012
R	24	Nov 12/2012	R	4	Nov 12/2012	R W6200	1	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 22
Nov 12/2012

91-21-11
WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
W6200 cont.			W6210 cont.			W6410 cont.		
R	2	Nov 12/2012	A	9	Nov 12/2012	R	4	Nov 12/2012
R	3	Nov 12/2012	A	10	Nov 12/2012	R	5	Nov 12/2012
R	4	Nov 12/2012	R W6220	1	Nov 12/2012	R	6	Nov 12/2012
R	5	Nov 12/2012	R	2	Nov 12/2012	R	7	Nov 12/2012
R	6	Nov 12/2012	R	3	Nov 12/2012	R	8	Nov 12/2012
R	7	Nov 12/2012	R	4	Nov 12/2012	R	9	Nov 12/2012
R	8	Nov 12/2012	R	5	Nov 12/2012	R	10	Nov 12/2012
R	9	Nov 12/2012	A	6	Nov 12/2012	R	11	Nov 12/2012
R	10	Nov 12/2012	R W6230	1	Nov 12/2012	R	12	Nov 12/2012
R	11	Nov 12/2012	R	2	Nov 12/2012	A	13	Nov 12/2012
R	12	Nov 12/2012	R	3	Nov 12/2012	A	14	Nov 12/2012
R	13	Nov 12/2012	R	4	Nov 12/2012	A	15	Nov 12/2012
R	14	Nov 12/2012	A	5	Nov 12/2012	R W6420	1	Nov 12/2012
R	15	Nov 12/2012	R W6240	1	Nov 12/2012	R	2	Nov 12/2012
R	16	Nov 12/2012	R	2	Nov 12/2012	R	3	Nov 12/2012
R	17	Nov 12/2012	R	3	Nov 12/2012	R W6430	1	Nov 12/2012
R	18	Nov 12/2012	R	4	Nov 12/2012	R W6490	1	Nov 12/2012
R	19	Nov 12/2012	R	5	Nov 12/2012	R	2	Nov 12/2012
R	20	Nov 12/2012	R	6	Nov 12/2012	R	3	Nov 12/2012
R W6210	1	Nov 12/2012	R	7	Nov 12/2012	R	4	Nov 12/2012
R	2	Nov 12/2012	R	8	Nov 12/2012	R	5	Nov 12/2012
R	3	Nov 12/2012	R	9	Nov 12/2012	R	6	Nov 12/2012
R	4	Nov 12/2012	R W6280	1	Nov 12/2012	R	7	Nov 12/2012
R	5	Nov 12/2012	R	2	Nov 12/2012	R	8	Nov 12/2012
R	6	Nov 12/2012	R W6410	1	Nov 12/2012	R	9	Nov 12/2012
R	7	Nov 12/2012	R	2	Nov 12/2012	R	10	Nov 12/2012
R	8	Nov 12/2012	R	3	Nov 12/2012	R W6500	1	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 23
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

91-21-11 WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
W6500 cont.			R W7050	1	Nov 12/2012	W7380 cont.		
R	2	Nov 12/2012	R	2	Nov 12/2012	R	3	Nov 12/2012
R	3	Nov 12/2012	R W7060	1	Nov 12/2012	R	4	Nov 12/2012
R	4	Nov 12/2012	R W7100	1	Nov 12/2012	R	5	Nov 12/2012
R	5	Nov 12/2012	R W7120	1	Nov 12/2012	R W7500	1	Nov 12/2012
R	6	Nov 12/2012	R	2	Nov 12/2012	R W7520	1	Nov 12/2012
R W6510	1	Nov 12/2012	R	3	Nov 12/2012	R	2	Nov 12/2012
R	2	Nov 12/2012	R	4	Nov 12/2012	R	3	Nov 12/2012
R W6520	1	Nov 12/2012	R	5	Nov 12/2012	R	4	Nov 12/2012
R	2	Nov 12/2012	R	6	Nov 12/2012	A	5	Nov 12/2012
R	3	Nov 12/2012	R	7	Nov 12/2012	R W7530	1	Nov 12/2012
R	4	Nov 12/2012	R	8	Nov 12/2012	R W7540	1	Nov 12/2012
R W6530	1	Nov 12/2012	R W7130	1	Nov 12/2012	R W7580	1	Nov 12/2012
R W6560	1	Nov 12/2012	R W7150	1	Nov 12/2012	R W7590	1	Nov 12/2012
R W6570	1	Nov 12/2012	R	2	Nov 12/2012	R	2	Nov 12/2012
R	2	Nov 12/2012	R W7180	1	Nov 12/2012	R	3	Nov 12/2012
R W6580	1	Nov 12/2012	R W7190	1	Nov 12/2012	R	4	Nov 12/2012
R	2	Nov 12/2012	R W7200	1	Nov 12/2012	R W7760	1	Nov 12/2012
R	3	Nov 12/2012	R	2	Nov 12/2012	R W8020	1	Nov 12/2012
R	4	Nov 12/2012	R	3	Nov 12/2012	R W8030	1	Nov 12/2012
R W6730	1	Nov 12/2012	R	4	Nov 12/2012	R	2	Nov 12/2012
R	2	Nov 12/2012	R	5	Nov 12/2012	R	3	Nov 12/2012
R	3	Nov 12/2012	R W7220	1	Nov 12/2012	R W8120	1	Nov 12/2012
R	4	Nov 12/2012	R W7230	1	Nov 12/2012	R	2	Nov 12/2012
R W7020	1	Nov 12/2012	R	2	Nov 12/2012	R	3	Nov 12/2012
R	2	Nov 12/2012	R W7350	1	Nov 12/2012	R	4	Nov 12/2012
R	3	Nov 12/2012	R W7380	1	Nov 12/2012	R	5	Nov 12/2012
R W7030	1	Nov 12/2012	R	2	Nov 12/2012	R	6	Nov 12/2012

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 24
Nov 12/2012

91-21-11
WIRE LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
W8120 cont.								
A	7	Nov 12/2012						
R W8130	1	Nov 12/2012						
R W8140	1	Nov 12/2012						
R W8150	1	Nov 12/2012						
R W8220	1	Nov 12/2012						
R	2	Nov 12/2012						
R	3	Nov 12/2012						
R	4	Nov 12/2012						
R	5	Nov 12/2012						
R	6	Nov 12/2012						
R	7	Nov 12/2012						
R	8	Nov 12/2012						
R	9	Nov 12/2012						
R W8230	1	Nov 12/2012						
R	2	Nov 12/2012						
R W8480	1	Nov 12/2012						
R	2	Nov 12/2012						
R W8520	1	Nov 12/2012						
R W8530	1	Nov 12/2012						
A	2	BLANK						

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280A108

EFFECTIVE PAGES

Page 25
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001			P1 - CAPTAINS INSTRUMENT PANEL											
0001	14	CQ			2-1	31-62-11	D03977B	58			GD03977	DC..	E		YC051-YD158, YN231
0001	14	CQ			2-3	31-62-11	D03977B	58			GD03977	DC..	E		YL951-YL954, YN232-YN235
0001	14	CQ			2-0	31-62-11	D03977B	58			GD03977	DC..	E		YL955-YL999, YN236-YR328
0002	16	PA			2-4	31-62-11	D03977B	53			GD0101A	ST..	1		YC051-YD158, YN231
0002	16	PA			2-9	31-62-11	D03977B	53			GD0101A	ST..	1		YL951-YL954, YN232-YN235
0002	16	PA			2-7	31-62-11	D03977B	53			GD0101A	ST..	1		YL955-YL999, YN236-YR328
0003	16	PA			2-4	31-62-11	D03977B	54			GD0101A	ST..	1		YC051-YD158, YN231
0003	16	PA			2-9	31-62-11	D03977B	54			GD0101A	ST..	1		YL951-YL954, YN232-YN235
0003	16	PA			2-7	31-62-11	D03977B	54			GD0101A	ST..	1		YL955-YL999, YN236-YR328
0004	16	PA			2-4	31-62-11	D03977B	55			GD0101A	ST..	1		YC051-YD158, YN231
0004	16	PA			2-9	31-62-11	D03977B	55			GD0101A	ST..	1		YL951-YL954, YN232-YN235
0004	16	PA			2-7	31-62-11	D03977B	55			GD0101A	ST..	1		YL955-YL999, YN236-YR328
0005	16	PA			2-4	31-62-11	D03977B	57			GD0101A	ST..	1		YC051-YD158, YN231
0005	16	PA			2-9	31-62-11	D03977B	57			GD0101A	ST..	1		YL951-YL954, YN232-YN235
0005	16	PA			2-7	31-62-11	D03977B	57			GD0101A	ST..	1		YL955-YL999, YN236-YR328
0006	14	GA			2-3	31-62-11	D03979B	58			GD03979	DC..	E		YC051-YC052
0006	14	PA			2-3	31-62-11	D03979B	58			GD03979	DC..	E		YC053-YD157
0006	14	CQ			2-3	31-62-11	D03979B	58			GD03979	DC..	E		YD158, YL951, YN231
0006	14	CQ			2-2	31-62-11	D03979B	58			GD03979	DC..	E		YL952-YL999, YN232-YR328
0007	16	PA			3-2	31-62-11	D03979B	53			GD0101A	ST..	1		YC051-YD158, YN231
0007	16	PA			3-3	31-62-11	D03979B	53			GD0101A	ST..	1		YL951-YL999, YN232-YR328
0008	16	PA			3-2	31-62-11	D03979B	54			GD0101A	ST..	1		YC051-YD158, YN231
0008	16	PA			3-3	31-62-11	D03979B	54			GD0101A	ST..	1		YL951-YL999, YN232-YR328
0009	16	PA			3-2	31-62-11	D03979B	55			GD0101A	ST..	1		YC051-YD158, YN231
0009	16	PA			3-3	31-62-11	D03979B	55			GD0101A	ST..	1		YL951-YL999, YN232-YR328

WIRE LIST

D280A108

91-21-11

Section W0000

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001			P1 - CAPTAINS INSTRUMENT PANEL (continued)											
0010	16	PA		3-2	31-62-11	D03979B		57			GD0101A	ST..	1		YC051-YD158, YN231
0010	16	PA		3-3	31-62-11	D03979B		57			GD0101A	ST..	1		YL951-YL999, YN232-YR328
0011	14	CQ		2-0	31-62-11	D03981B		58			GD03981	DC..	E		YC051-YD158, YL952-YR328
0011	14	CQ		1-11	31-62-11	D03981B		58			GD03981	DC..	E		YL951
0012	16	PA		4-2	31-62-11	D03981B		53			GD0201A	ST..	1		YC051-YD158, YN231
0012	16	PA		4-0	31-62-11	D03981B		53			GD0201A	ST..	1		YL951-YL999, YN232-YR328
0013	16	PA		4-2	31-62-11	D03981B		54			GD0201A	ST..	1		YC051-YD158, YN231
0013	16	PA		4-0	31-62-11	D03981B		54			GD0201A	ST..	1		YL951-YL999, YN232-YR328
0014	16	PA		4-2	31-62-11	D03981B		55			GD0201A	ST..	1		YC051-YD158, YN231
0014	16	PA		4-0	31-62-11	D03981B		55			GD0201A	ST..	1		YL951-YL999, YN232-YR328
0015	16	PA		4-2	31-62-11	D03981B		57			GD0201A	ST..	1		YC051-YD158, YN231
0015	16	PA		4-0	31-62-11	D03981B		57			GD0201A	ST..	1		YL951-YL999, YN232-YR328
0016	20	PA		5-5	31-62-11	D40738J		27			GD0101B	ST..	1A		YC051-YD158, YN231
0016	20	PA		3-9	31-62-11	D40738J		27			GD0101B	ST..	1A		YL951-YL954, YN232-YN235
0016	20	PA		5-1	31-62-11	D40738J		27			GD0101B	ST..	1A		YL955-YL999, YN236-YR328
0032	22	PA		4-2	31-62-12	D03981B		A01			GD0201C	DC..	1A		YC051-YD158, YN231
0032	22	PA		4-1	31-62-12	D03981B		A01			GD0201C	DC..	1A		YL951-YL999, YN232-YR328
0033	22	PA		4-2	31-62-12	D03981B		B01			GD0201C	DC..	1A		YC051-YD158, YN231
0033	22	PA		4-1	31-62-12	D03981B		B01			GD0201C	DC..	1A		YL951-YL999, YN232-YR328
0034	22	PA		2-4	31-62-12	D03977B		A01			GD0101C	DC..	1A		YC051-YD158, YN231
0034	22	PA		2-7	31-62-12	D03977B		A01			GD0101C	DC..	1A		YL951-YL999, YN232-YR328
0035	22	PA		2-4	31-62-12	D03977B		E01			GD0101C	DC..	1A		YC051-YD158, YN231
0035	22	PA		2-7	31-62-12	D03977B		E01			GD0101C	DC..	1A		YL951-YL999, YN232-YR328
0036	22	G5		3-2	31-62-12	D03979B		B01			GD0101D	DC..	1A		YC051-YD158, YN231
0036	22	G5		3-1	31-62-12	D03979B		B01			GD0101D	DC..	1A		YL951-YL954, YN232-YN235

WIRE LIST

D280A108

91-21-11

Section W0000

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001			P1 - CAPTAINS INSTRUMENT PANEL (continued)											
0036	22		G5		3-5	31-62-12	D03979B	B01			GD0101D	DC..	1A		YL955-YL999, YN236-YR328
0037	22		G5		3-2	31-62-12	D03979B	E01			GD0101D	DC..	1A		YC051-YD158, YN231
0037	22		G5		3-1	31-62-12	D03979B	E01			GD0101D	DC..	1A		YL951-YL954, YN232-YN235
0037	22		G5		3-5	31-62-12	D03979B	E01			GD0101D	DC..	1A		YL955-YL999, YN236-YR328
0046	22		PA		4-1	31-62-13	D03999	7			GD0301D	DC..	1A		YC051-YD158, YN231
0046	22		PA		5-2	31-62-13	D03999	7			GD0301D	DC..	1A		YL951
0046	22		PA		5-3	31-62-13	D03999	7			GD0301D	DC..	1A		YL952-YL954, YN232-YN235
0046	22		PA		6-2	31-62-13	D03999	7			GD0301D	DC..	1A		YL955-YL999, YN236-YR328
0047	22		PA		4-1	31-62-13	D03999	12			GD0301D	DC..	1A		YC051-YD158, YN231
0047	22		PA		5-2	31-62-13	D03999	12			GD0301D	DC..	1A		YL951
0047	22		PA		5-3	31-62-13	D03999	12			GD0301D	DC..	1A		YL952-YL954, YN232-YN235
0047	22		PA		6-2	31-62-13	D03999	12			GD0301D	DC..	1A		YL955-YL999, YN236-YR328
0048	22		PA		6-6	31-62-13	D00331	10			GD0201C	DC..	1A		YC051-YD158, YN231
0048	22		PA		6-4	31-62-13	D00331	10			GD0201C	DC..	1A		YL951-YL999, YN232-YR328
0049	22		PA		6-6	31-62-13	D00331	14			GD0201C	DC..	1A		YC051-YD158, YN231
0049	22		PA		6-4	31-62-13	D00331	14			GD0201C	DC..	1A		YL951-YL999, YN232-YR328
0050	22		PA		6-6	31-62-13	D00331	1			GD0201C	DC..	1A		YC051-YD158, YN231
0050	22		PA		6-4	31-62-13	D00331	1			GD0201C	DC..	1A		YL951-YL999, YN232-YR328
0051	22		PA		6-6	31-62-13	D00331	5			GD0201C	DC..	1A		YC051-YD158, YN231
0051	22		PA		6-4	31-62-13	D00331	5			GD0201C	DC..	1A		YL951-YL999, YN232-YR328
0052	22		PA		6-6	31-62-13	D00331	20			GD0201C	DC..	1A		YC051-YD158, YN231
0052	22		PA		6-4	31-62-13	D00331	20			GD0201C	DC..	1A		YL951-YL999, YN232-YR328
0053	22		PA		6-9	31-62-13	D00339	11			GD0101C	DC..	1A		YC051-YD158, YL951, YN231
0053	22		PA		6-10	31-62-13	D00339	11			GD0101C	DC..	1A		YL952-YL954, YN232-YN235

WIRE LIST

D280A108

91-21-11

Section W0000

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)										
0053	22		PA		6-11	31-62-13	D00339	11			GD0101C	DC..	1A		YL955-YL999, YN236-YR328
0054	22		PA		4-3	31-62-13	D00423	17			GD0101C	DC..	1A		YC051-YD158, YN231
0054	22		PA		4-10	31-62-13	D00423	17			GD0101C	DC..	1A		YL951
0054	22		PA		4-11	31-62-13	D00423	17			GD0101C	DC..	1A		YL952-YL954, YN232-YN235
0054	22		PA		5-0	31-62-13	D00423	17			GD0101C	DC..	1A		YL955-YL999, YN236-YR328
0055	22		PA		4-3	31-62-13	D00423	22			GD0101C	DC..	1A		YC051-YD158, YN231
0055	22		PA		4-10	31-62-13	D00423	22			GD0101C	DC..	1A		YL951
0055	22		PA		4-11	31-62-13	D00423	22			GD0101C	DC..	1A		YL952-YL954, YN232-YN235
0055	22		PA		5-0	31-62-13	D00423	22			GD0101C	DC..	1A		YL955-YL999, YN236-YR328
0060	22		PA		18-3	21-33-11	D40578J	19			D03999		17		YC060-YC064
0060	22		PA		9-4	21-33-11	D40578J	19			D03999		17		YL951
0060	22		PA		9-0	21-33-11	D40578J	19			D03999		17		YL952-YR328
0062	22		PA		18-3	31-53-11	D40578J	39			D03999		19		YC060-YC064
0062	22		PA		9-4	31-53-11	D40578J	39			D03999		19		YL951
0062	22		PA		9-0	31-53-11	D40578J	39			D03999		19		YL952-YR328
0078	22		CQ		4-11	22-14-11	D02437	6			TB0101Z	A021	1A		YC051-YD158, YL952-YL954, YN231-YN235
0078	22		CQ		4-10	22-14-11	D02437	6			TB0101Z	A021	1A		YL951
0078	22		CQ		4-6	22-14-11	D02437	6			TB0101Z	A021	1A		YL955-YL999, YN236-YR328
0079	22		CQ		4-11	22-14-11	D02437	7			TB0101Z	A021	1A		YC051-YD158, YL952-YL954, YN231-YN235
0079	22		CQ		4-10	22-14-11	D02437	7			TB0101Z	A021	1A		YL951
0079	22		CQ		4-6	22-14-11	D02437	7			TB0101Z	A021	1A		YL955-YL999, YN236-YR328
0080	22		CQ		5-0	22-14-11	D02435	13			TB0101Z	A021	1A		YC051-YD158, YL952-YL954, YN231-YN235
0080	22		CQ		4-11	22-14-11	D02435	13			TB0101Z	A021	1A		YL951
0080	22		CQ		4-7	22-14-11	D02435	13			TB0101Z	A021	1A		YL955-YL999, YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W0000

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)												
0081	22		CQ		5-0	22-14-11	D02435		14		TB0101Z	A021	1A		YC051-YD158, YL952-YL954, YN231-YN235		
0081	22		CQ		4-11	22-14-11	D02435		14		TB0101Z	A021	1A		YL951		
0081	22		CQ		4-7	22-14-11	D02435		14		TB0101Z	A021	1A		YL955-YL999, YN236-YR328		
0082	22		CQ		5-0	22-14-11	D02435		4		TB0101Z	A021	1A		YC051-YD158, YL952-YL954, YN231-YN235		
0082	22		CQ		4-11	22-14-11	D02435		4		TB0101Z	A021	1A		YL951		
0082	22		CQ		4-7	22-14-11	D02435		4		TB0101Z	A021	1A		YL955-YL999, YN236-YR328		
0083	22		G5		5-1	22-14-11	D02435		5		TB0101Y	A015	1A		YC051-YD158, YN231		
0083	22		G5		5-0	22-14-11	D02435		5		TB0101Y	A015	1A		YL951		
0083	22		G5		5-3	22-14-11	D02435		5		TB0101Y	A015	1A		YL952-YL954, YN232-YN235		
0083	22		G5		4-8	22-14-11	D02435		5		TB0101Y	A015	1A		YL955-YL999, YN236-YR328		
0084	22		G5		5-1	22-14-11	D02435		6		TB0101Y	A015	1A		YC051-YD158, YN231		
0084	22		G5		5-0	22-14-11	D02435		6		TB0101Y	A015	1A		YL951		
0084	22		G5		5-3	22-14-11	D02435		6		TB0101Y	A015	1A		YL952-YL954, YN232-YN235		
0084	22		G5		4-8	22-14-11	D02435		6		TB0101Y	A015	1A		YL955-YL999, YN236-YR328		
0085	22		G5		5-1	22-14-11	D02435		7		TB0101Y	B015	1A		YC051-YD158, YN231		
0085	22		G5		5-0	22-14-11	D02435		7		TB0101Y	B015	1A		YL951		
0085	22		G5		5-3	22-14-11	D02435		7		TB0101Y	B015	1A		YL952-YL954, YN232-YN235		
0085	22		G5		4-8	22-14-11	D02435		7		TB0101Y	B015	1A		YL955-YL999, YN236-YR328		
0086	22		G5		5-1	22-14-11	D02435		8		TB0101Y	B015	1A		YC051-YD158, YN231		
0086	22		G5		5-0	22-14-11	D02435		8		TB0101Y	B015	1A		YL951		
0086	22		G5		5-3	22-14-11	D02435		8		TB0101Y	B015	1A		YL952-YL954, YN232-YN235		
0086	22		G5		4-8	22-14-11	D02435		8		TB0101Y	B015	1A		YL955-YL999, YN236-YR328		
0087	22		G5		8-4	22-14-11	D02435		9		D04221J		5		YC051-YD158, YN231		
0087	22		G5		8-5	22-14-11	D02435		9		D04221J		5		YL951		

WIRE LIST

D280A108

91-21-11

Section W0000

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)										
0087	22		G5		8-2	22-14-11	D02435		9		D04221J		5		YL952-YL999, YN232-YR328
0088	22		CQ		5-0	22-14-11	D02435		11		TB0101Y	A019	1A		YC051-YD158, YN231
0088	22		CQ		4-11	22-14-11	D02435		11		TB0101Y	A019	1A		YL951
0088	22		CQ		5-1	22-14-11	D02435		11		TB0101Y	A019	1A		YL952-YL954, YN232-YN235
0088	22		CQ		4-7	22-14-11	D02435		11		TB0101Y	A019	1A		YL955-YL999, YN236-YR328
0089	20		CQ		4-2	22-14-11	D02435		3		GD0101B	DC..	1A		YC051-YD158, YN231
0089	20		CQ		4-9	22-14-11	D02435		3		GD0101B	DC..	1A		YL951
0089	20		CQ		4-10	22-14-11	D02435		3		GD0101B	DC..	1A		YL952-YL999, YN232-YR328
0091	22		CQ		6-2	22-14-11	D04221J		2		TB0101Z	A021	1A		YC051-YD158, YL951, YN231
0091	22		CQ		6-3	22-14-11	D04221J		2		TB0101Z	A021	1A		YL952-YL954, YN232-YN235
0091	22		CQ		5-4	22-14-11	D04221J		2		TB0101Z	A021	1A		YL955-YL999, YN236-YR328
0092	22		G5		6-3	22-14-11	D04221J		3		TB0101Y	A015	1A		YC051-YD158, YL951, YN231
0092	22		G5		6-6	22-14-11	D04221J		3		TB0101Y	A015	1A		YL952-YL954, YN232-YN235
0092	22		G5		5-5	22-14-11	D04221J		3		TB0101Y	A015	1A		YL955-YL999, YN236-YR328
0093	22		G5		6-3	22-14-11	D04221J		4		TB0101Y	B015	1A		YC051-YD158, YL951, YN231
0093	22		G5		6-6	22-14-11	D04221J		4		TB0101Y	B015	1A		YL952-YL954, YN232-YN235
0093	22		G5		5-5	22-14-11	D04221J		4		TB0101Y	B015	1A		YL955-YL999, YN236-YR328
0094	22		CQ		6-2	22-14-11	D04221J		6		TB0101Y	A019	1A		YC051-YD158, YL951, YN231
0094	22		CQ		6-4	22-14-11	D04221J		6		TB0101Y	A019	1A		YL952-YL954, YN232-YN235
0094	22		CQ		5-4	22-14-11	D04221J		6		TB0101Y	A019	1A		YL955-YL999, YN236-YR328
0095	22		CQ		6-2	22-14-11	D04221J		7		TB0101Y	A019	1A		YC051-YD158, YL951, YN231

WIRE LIST
D280A108

91-21-11
Section W0000
Page 6
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)										
0095	22		CQ		6-4	22-14-11	D04221J	7			TB0101Y	A019	1A		YL952-YL954, YN232-YN235
0095	22		CQ		5-4	22-14-11	D04221J	7			TB0101Y	A019	1A		YL955-YL999, YN236-YR328
0096	24		PK		6-9	32-44-11	D40824J	27			D40578J	11			YC051-YD158, YN231
0096	24		PK		7-0	32-44-11	D40824J	27			D40578J	11			YL951-YL999, YN232-YR328
0097	22		CQ		8-7	22-14-11	D02439	11			TB0101Y	A019	1A		YC051-YD158, YL952-YL954, YN231-YN235
0097	22		CQ		8-8	22-14-11	D02439	11			TB0101Y	A019	1A		YL951
0097	22		CQ		8-1	22-14-11	D02439	11			TB0101Y	A019	1A		YL955-YL999, YN236-YR328
0098	20		PA		8-5	22-23-12	D00319	8			D41833J	8			YC051-YD158, YN231
0098	20		PA		8-6	22-23-12	D00319	8			D41833J	8			YL951
0098	20		PA		8-3	22-23-12	D00319	8			D41833J	8			YL952-YL959, YN232-YN235
0099	20		PA		7-6	22-23-12	D00319	12			GD0201B	AC..	1A		YC051-YD158, YL951, YN231
0099	20		PA		7-3	22-23-12	D00319	12			GD0201B	AC..	1A		YL952-YL959, YN232-YN235
0100	22		PA		8-4	22-31-11	D02435	15			D04221J	8			YC051-YD155
0100	22		G5		5-0	22-14-11	D02435	15			TB0101Y	A003	1A		YD157-YD158, YN231
0100	22		G5		5-3	22-14-11	D02435	15			TB0101Y	A003	1A		YL951
0100	22		G5		5-5	22-14-11	D02435	15			TB0101Y	A003	1A		YL952-YL954, YN232-YN235
0100	22		G5		4-11	22-14-11	D02435	15			TB0101Y	A003	1A		YL955-YL999, YN236-YR328
0101	22		PA		8-4	22-31-51	D02435	10			D04221J	9			YC051-YD158, YN231
0101	22		PA		8-5	22-31-51	D02435	10			D04221J	9			YL951
0101	22		PA		8-2	22-31-51	D02435	10			D04221J	9			YL952-YL999, YN232-YR328
0102	22		G5		6-2	22-14-11	D04221J	8			TB0101Y	A003	1A		YD157-YD158, YL955-YN231, YN236-YR328
0102	22		G5		6-6	22-14-11	D04221J	8			TB0101Y	A003	1A		YL951
0102	22		G5		6-8	22-14-11	D04221J	8			TB0101Y	A003	1A		YL952-YL954, YN232-YN235
0103	22		PA		4-11	34-61-16	D02437	14			TB0101Y	A007	1A		YC051-YD158, YN231

WIRE LIST

D280A108

91-21-11

Section W0000

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)										
0103	22		PA		5-1	34-61-16	D02437		14		TB0101Y	A007	1A		YL951
0103	22		PA		5-3	34-61-16	D02437		14		TB0101Y	A007	1A		YL952-YL954, YN232-YN235
0103	22		PA		4-9	34-61-16	D02437		14		TB0101Y	A007	1A		YL955-YL999, YN236-YR328
0104	22		PA		4-1	34-61-16	D02437		3		GD0101B	DC..	1A		YC051-YD158, YN231
0104	22		PA		4-8	34-61-16	D02437		3		GD0101B	DC..	1A		YL951
0104	22		PA		4-9	34-61-16	D02437		3		GD0101B	DC..	1A		YL952-YL999, YN232-YR328
0105	22		PA		4-11	34-61-16	D02437		9		TB0101Y	B007	1A		YC051-YD158, YN231
0105	22		PA		5-1	34-61-16	D02437		9		TB0101Y	B007	1A		YL951
0105	22		PA		5-3	34-61-16	D02437		9		TB0101Y	B007	1A		YL952-YL954, YN232-YN235
0105	22		PA		4-9	34-61-16	D02437		9		TB0101Y	B007	1A		YL955-YL999, YN236-YR328
0106	22		PA		10-7	34-61-16	D02437		5		D02441		5		YC051-YD158, YN231
0106	22		PA		10-11	34-61-16	D02437		5		D02441		5		YL951
0106	22		PA		10-4	34-61-16	D02437		5		D02441		5		YL952-YL999, YN232-YR328
0107	22		PA		6-2	34-61-16	D04221J		10		TB0101Y	A007	1A		YC051-YD158, YN231
0107	22		PA		6-5	34-61-16	D04221J		10		TB0101Y	A007	1A		YL951
0107	22		PA		6-7	34-61-16	D04221J		10		TB0101Y	A007	1A		YL952-YL954, YN232-YN235
0107	22		PA		6-1	34-61-16	D04221J		10		TB0101Y	A007	1A		YL955-YL999, YN236-YR328
0108	22		PA		6-2	34-61-16	D04221J		11		TB0101Y	B007	1A		YC051-YD158, YN231
0108	22		PA		6-5	34-61-16	D04221J		11		TB0101Y	B007	1A		YL951
0108	22		PA		6-7	34-61-16	D04221J		11		TB0101Y	B007	1A		YL952-YL954, YN232-YN235
0108	22		PA		6-1	34-61-16	D04221J		11		TB0101Y	B007	1A		YL955-YL999, YN236-YR328
0110	22		PA		8-6	34-61-16	D02441		9		TB0101Y	B007	1A		YC051-YD158, YN231
0110	22		PA		9-0	34-61-16	D02441		9		TB0101Y	B007	1A		YL951
0110	22		PA		8-11	34-61-16	D02441		9		TB0101Y	B007	1A		YL952-YL954, YN232-YN235
0110	22		PA		8-4	34-61-16	D02441		9		TB0101Y	B007	1A		YL955-YL999, YN236-YR328
0111	22		PA		8-6	34-61-16	D02441		14		TB0101Y	A007	1A		YC051-YD158, YN231
0111	22		PA		9-0	34-61-16	D02441		14		TB0101Y	A007	1A		YL951

WIRE LIST

D280A108

91-21-11

Section W0000

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)												
0111	22		PA		8-11	34-61-16	D02441		14			TB0101Y	A007	1A		YL952-YL954, YN232-YN235	
0111	22		PA		8-4	34-61-16	D02441		14			TB0101Y	A007	1A		YL955-YL999, YN236-YR328	
0133	24		PK		7-2	32-41-11	D00339		8			D40578J	10			YC051-YD158, YN231	
0133	24		PK		7-3	32-41-11	D00339		8			D40578J	10			YL951-YL999, YN232-YR328	
0134	24		PK		7-2	32-42-11	D00339		9			D40914J	1			YC051-YD158, YL951-YR328	
0135	24		G6		7-9	32-42-11	D00331		26			D46033J	6			YC051-YD158, YL951, YN231	
0135	24		G6		7-10	32-42-11	D00331		26			D46033J	6			YL952-YL999, YN232-YR328	
0136	24		PK		7-1	32-42-11	D00331		25			D40914J	2			YC051-YD158, YN231	
0136	24		PK		7-0	32-42-11	D00331		25			D40914J	2			YL951-YL999, YN232-YR328	
0137	22		G5		6-11	32-42-11	D00333		38			GD0201B	DC..	1A		YC051-YD158, YN231	
0137	22		G5		6-8	32-42-11	D00333		38			GD0201B	DC..	1A		YL951-YL999, YN232-YR328	
0138	24		G6		7-7	32-42-11	D00333		32			D40914J	3			YC051-YD158, YN231	
0138	24		G6		7-6	32-42-11	D00333		32			D40914J	3			YL951	
0138	24		G6		7-5	32-42-11	D00333		32			D40914J	3			YL952-YL999, YN232-YR328	
0139	24		G6		7-7	32-42-11	D00333		33			D40914J	4			YC051-YD158, YN231	
0139	24		G6		7-6	32-42-11	D00333		33			D40914J	4			YL951	
0139	24		G6		7-5	32-42-11	D00333		33			D40914J	4			YL952-YL999, YN232-YR328	
0140	24		G6		7-7	32-42-11	D00333		36			D40914J	5			YC051-YD158, YN231	
0140	24		G6		7-6	32-42-11	D00333		36			D40914J	5			YL951	
0140	24		G6		7-5	32-42-11	D00333		36			D40914J	5			YL952-YL999, YN232-YR328	
0141	24		G6		7-7	32-42-11	D00333		34			D40914J	6			YC051-YD158, YN231	
0141	24		G6		7-6	32-42-11	D00333		34			D40914J	6			YL951	
0141	24		G6		7-5	32-42-11	D00333		34			D40914J	6			YL952-YL999, YN232-YR328	
0142	24		G6		7-7	32-42-11	D00333		35			D40914J	7			YC051-YD158, YN231	
0142	24		G6		7-6	32-42-11	D00333		35			D40914J	7			YL951	
0142	24		G6		7-5	32-42-11	D00333		35			D40914J	7			YL952-YL999, YN232-YR328	

WIRE LIST

D280A108

91-21-11

Section W0000

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)										
0143	24		G6		7-7	32-42-11	D00333		37		D40914J		8		YC051-YD158, YN231
0143	24		G6		7-6	32-42-11	D00333		37		D40914J		8		YL951
0143	24		G6		7-5	32-42-11	D00333		37		D40914J		8		YL952-YL999, YN232-YR328
0144	24		PK		7-1	32-42-11	D00331		24		D40914J		9		YC051-YD158, YN231
0144	24		PK		7-0	32-42-11	D00331		24		D40914J		9		YL951-YL999, YN232-YR328
0145	22		PA		6-5	32-42-11	D00331		31		GD0201B	DC..	1A		YC051-YD158, YN231
0145	22		PA		6-3	32-42-11	D00331		31		GD0201B	DC..	1A		YL951-YL999, YN232-YR328
0146	22		PA		6-5	32-42-11	D00331		29		GD0201B	DC..	1A		YC051-YD158, YN231
0146	22		PA		6-3	32-42-11	D00331		29		GD0201B	DC..	1A		YL951-YL999, YN232-YR328
0147	24		PK		7-1	32-42-11	D00331		30		D40914J		10		YC051-YD158, YN231
0147	24		PK		7-0	32-42-11	D00331		30		D40914J		10		YL951-YL999, YN232-YR328
0148	24		PK		7-1	32-42-11	D00331		28		D40914J		11		YC051-YD158, YN231
0148	24		PK		7-0	32-42-11	D00331		28		D40914J		11		YL951-YL999, YN232-YR328
0152	24		PK		4-10	32-64-11	D40578J		2		TB0201Z	A001	1A		YC051-YD158, YN231
0152	24		PK		4-11	32-64-11	D40578J		2		TB0201Z	A001	1A		YL951
0152	24		PK		5-0	32-64-11	D40578J		2		TB0201Z	A001	1A		YL952-YL999, YN232-YR328
0154	24		PK		7-3	32-64-11	D11732		9		D40578J		4		YC051-YD158, YN231
0154	24		PK		7-5	32-64-11	D11732		9		D40578J		4		YL951
0154	24		PK		7-4	32-64-11	D11732		9		D40578J		4		YL952-YL999, YN232-YR328
0155	24		PK		7-3	32-64-11	D11732		22		D40578J		5		YC051-YD158, YN231
0155	24		PK		7-5	32-64-11	D11732		22		D40578J		5		YL951
0155	24		PK		7-4	32-64-11	D11732		22		D40578J		5		YL952-YL999, YN232-YR328
0156	24		PK		7-3	32-64-11	D11732		23		D40578J		6		YC051-YD158, YN231
0156	24		PK		7-5	32-64-11	D11732		23		D40578J		6		YL951
0156	24		PK		7-4	32-64-11	D11732		23		D40578J		6		YL952-YL999, YN232-YR328
0157	24		PK		7-3	32-64-11	D11732		30		D40578J		7		YC051-YD158, YN231
0157	24		PK		7-5	32-64-11	D11732		30		D40578J		7		YL951
0157	24		PK		7-4	32-64-11	D11732		30		D40578J		7		YL952-YL999, YN232-YR328

WIRE LIST

D280A108

91-21-11

Section W0000

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001			P1 - CAPTAINS INSTRUMENT PANEL (continued)											
0158	24		PK		7-3	32-64-11	D11732	31			D40578J	8			YC051-YD158, YN231
0158	24		PK		7-5	32-64-11	D11732	31			D40578J	8			YL951
0158	24		PK		7-4	32-64-11	D11732	31			D40578J	8			YL952-YL999, YN232-YR328
0159	24		PK		7-3	32-64-11	D11732	19			D40578J	9			YC051-YD158, YN231
0159	24		PK		7-5	32-64-11	D11732	19			D40578J	9			YL951
0159	24		PK		7-4	32-64-11	D11732	19			D40578J	9			YL952-YL999, YN232-YR328
0161	22		PA		5-0	34-45-11	D04221J	30			TB0201Z	A001	1A		YC051-YD158, YL951, YN231
0161	22		PA		5-1	34-45-11	D04221J	30			TB0201Z	A001	1A		YL952-YL999, YN232-YR328
0162	24		PK		6-4	34-49-11	D04221J	12			TB0101Y	A009	1A		YC051-YD158, YN231
0162	24		PK		6-5	34-49-11	D04221J	12			TB0101Y	A009	1A		YL951
0162	24		PK		6-6	34-49-11	D04221J	12			TB0101Y	A009	1A		YL952-YL954, YN232-YN235
0162	24		PK		6-0	34-49-11	D04221J	12			TB0101Y	A009	1A		YL955-YL999, YN236-YR328
0163	24		PK		6-4	34-49-11	D04221J	17			TB0101Y	B009	1A		YC051-YD158, YN231
0163	24		PK		6-5	34-49-11	D04221J	17			TB0101Y	B009	1A		YL951
0163	24		PK		6-6	34-49-11	D04221J	17			TB0101Y	B009	1A		YL952-YL954, YN232-YN235
0163	24		PK		6-0	34-49-11	D04221J	17			TB0101Y	B009	1A		YL955-YL999, YN236-YR328
0164	24		PK		5-3	34-49-11	D00423	5			TB0101Y	A009	1A		YC051-YD158, YN231
0164	24		PK		5-4	34-49-11	D00423	5			TB0101Y	A009	1A		YL951
0164	24		PK		5-5	34-49-11	D00423	5			TB0101Y	A009	1A		YL952-YL954, YN232-YN235
0164	24		PK		4-11	34-49-11	D00423	5			TB0101Y	A009	1A		YL955-YL999, YN236-YR328
0165	24		PK		5-3	34-49-11	D00423	6			TB0101Y	B009	1A		YC051-YD158, YN231
0165	24		PK		5-4	34-49-11	D00423	6			TB0101Y	B009	1A		YL951
0165	24		PK		5-5	34-49-11	D00423	6			TB0101Y	B009	1A		YL952-YL954, YN232-YN235
0165	24		PK		4-11	34-49-11	D00423	6			TB0101Y	B009	1A		YL955-YL999, YN236-YR328
0166	22		PA		4-3	34-49-11	D00423	4			GD0101B	DC..	1A		YC051-YD158, YN231
0166	22		PA		4-11	34-49-11	D00423	4			GD0101B	DC..	1A		YL951

WIRE LIST

D280A108

91-21-11

Section W0000

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)										
0166	22		PA		5-0	34-49-11	D00423		4		GD0101B	DC..	1A		YL952-YL999, YN232-YR328
0168	22		PA		4-9	34-41-11	D04207J		33		TB0201Z	A001	1A		YC051-YC052
0168	22		PA		4-9	SPARE	D04207J		33		TB0201Z	A001	1A		YC053-YD158, YN231
0168	22		PA		4-10	SPARE	D04207J		33		TB0201Z	A001	1A		YL951-YL999, YN232-YR328
0169	24		B6		8-0	31-22-11	D00714		3		TB3092Y	A009	1A		YC051-YD158, YN231
0169	24		B6		7-11	31-22-11	D00714		3		TB3092Y	A009	1A		YL951
0169	24		B6		8-1	31-22-11	D00714		3		TB3092Y	A009	1A		YL952-YL954, YN232-YN235
0169	24		B6		7-6	31-22-11	D00714		3		TB3092Y	A009	1A		YL955-YL999, YN236-YR328
0170	24		B6		8-0	31-22-11	D00714		8		TB3092Y	B009	1A		YC051-YD158, YN231
0170	24		B6		7-11	31-22-11	D00714		8		TB3092Y	B009	1A		YL951
0170	24		B6		8-1	31-22-11	D00714		8		TB3092Y	B009	1A		YL952-YL954, YN232-YN235
0170	24		B6		7-6	31-22-11	D00714		8		TB3092Y	B009	1A		YL955-YL999, YN236-YR328
0171	24		B6		0-7	31-22-11	D00714		13		D00714		14		YC051-YD158, YL951-YR328
0172	20		CQ		4-4	31-22-11	D00714		7		GD0101B	ST..	1A		YC051-YD158, YN231
0172	20		CQ		3-0	31-22-11	D00714		7		GD0101B	ST..	1A		YL951-YL954, YN232-YN235
0172	20		CQ		2-7	31-22-11	D00714		7		GD0101B	ST..	1A		YL955-YL999, YN236-YR328
0173	20		CQ		4-4	31-22-11	D00714		9		GD0101B	DC..	1A		YC051-YD158, YN231
0173	20		CQ		3-0	31-22-11	D00714		9		GD0101B	DC..	1A		YL951-YL954, YN232-YN235
0173	20		CQ		2-7	31-22-11	D00714		9		GD0101B	DC..	1A		YL955-YL999, YN236-YR328
0174	20		CQ		9-0	31-52-11	D40738J		4		D40924J		24		YC051-YD158, YN231
0174	20		CQ		8-5	31-52-11	D40738J		4		D40924J		24		YL951-YL954, YN232-YN235
0174	20		CQ		8-6	31-52-11	D40738J		4		D40924J		24		YL955-YL999, YN236-YR328
0175	20		CQ		11-11	31-52-11	D40738J		5		D40740J		5		YC051-YD158, YN231
0175	20		CQ		10-8	31-52-11	D40738J		5		D40740J		5		YL951-YL954, YN232-YN235

WIRE LIST

D280A108

91-21-11
Section W0000
Page 12
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)										
0175	20		CQ		10-10	31-52-11	D40738J	5			D40740J	5			YL955-YL999, YN236-YR328
0176	20		CQ		9-2	31-52-11	D40738J	6			TB3092Y	B019	1A		YC051-YD158, YN231
0176	20		CQ		8-10	31-52-11	D40738J	6			TB3092Y	B019	1A		YL951
0176	20		CQ		9-0	31-52-11	D40738J	6			TB3092Y	B019	1A		YL952-YL954, YN232-YN235
0176	20		CQ		8-6	31-52-11	D40738J	6			TB3092Y	B019	1A		YL955-YL999, YN236-YR328
0177	20		CQ		9-2	31-52-11	D40738J	7			TB3092Z	B021	1A		YC051-YD158, YN231
0177	20		CQ		8-11	31-52-11	D40738J	7			TB3092Z	B021	1A		YL951
0177	20		CQ		9-1	31-52-11	D40738J	7			TB3092Z	B021	1A		YL952-YL954, YN232-YN235
0177	20		CQ		8-7	31-52-11	D40738J	7			TB3092Z	B021	1A		YL955-YL999, YN236-YR328
0178	20		CQ		9-2	31-52-11	D40738J	1			TB3092Y	A019	1A		YC051-YD158, YN231
0178	20		CQ		8-10	31-52-11	D40738J	1			TB3092Y	A019	1A		YL951
0178	20		CQ		9-0	31-52-11	D40738J	1			TB3092Y	A019	1A		YL952-YL954, YN232-YN235
0178	20		CQ		8-6	31-52-11	D40738J	1			TB3092Y	A019	1A		YL955-YL999, YN236-YR328
0179	20		CQ		4-2	31-52-11	D40738J	2			GD1010C	DC..	1A		YC051-YD158, YN231
0179	20		CQ		3-8	31-52-11	D40738J	2			GD1010C	DC..	1A		YL951-YL954, YN232-YN235
0179	20		CQ		5-5	31-52-11	D40738J	2			GD1010C	DC..	1A		YL955-YL999, YN236-YR328
0180	20		CQ		9-2	31-52-11	D40738J	3			TB3092Z	B021	1A		YC051-YD158, YN231
0180	20		CQ		8-11	31-52-11	D40738J	3			TB3092Z	B021	1A		YL951
0180	20		CQ		9-1	31-52-11	D40738J	3			TB3092Z	B021	1A		YL952-YL954, YN232-YN235
0180	20		CQ		8-7	31-52-11	D40738J	3			TB3092Z	B021	1A		YL955-YL999, YN236-YR328
0181	20		CQ		9-4	31-52-25	D40738J	8			D40824J	1			YC051-YD158, YN231
0181	20		CQ		8-10	31-52-25	D40738J	8			D40824J	1			YL951-YL954, YN232-YN235
0181	20		CQ		8-11	31-52-25	D40738J	8			D40824J	1			YL955-YL999, YN236-YR328
0182	20		CQ		9-4	31-52-31	D40738J	11			D40824J	16			YC051-YD158, YN231
0182	20		CQ		8-10	31-52-31	D40738J	11			D40824J	16			YL951-YL954, YN232-YN235

WIRE LIST

D280A108

91-21-11

Section W0000

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)										
0182	20		CQ		8-11	31-52-31	D40738J	11			D40824J	16			YL955-YL999, YN236-YR328
0183	20		CQ		9-4	31-52-35	D40738J	12			D40824J	17			YC051-YD158, YN231
0183	20		CQ		8-10	31-52-35	D40738J	12			D40824J	17			YL951-YL954, YN232-YN235
0183	20		CQ		8-11	31-52-35	D40738J	12			D40824J	17			YL955-YL999, YN236-YR328
0184	20		CQ		9-4	31-52-41	D40738J	10			D40824J	18			YC051-YD158, YN231
0184	20		CQ		8-10	31-52-41	D40738J	10			D40824J	18			YL951-YL954, YN232-YN235
0184	20		CQ		8-11	31-52-41	D40738J	10			D40824J	18			YL955-YL999, YN236-YR328
0185	20		CQ		9-4	31-52-45	D40738J	13			D40824J	6			YC051-YD158, YN231
0185	20		CQ		8-10	31-52-45	D40738J	13			D40824J	6			YL951-YL954, YN232-YN235
0185	20		CQ		8-11	31-52-45	D40738J	13			D40824J	6			YL955-YL999, YN236-YR328
0186	20		CQ		9-4	31-52-71	D40738J	9			D40824J	15			YC051-YD158, YN231
0186	20		CQ		8-10	31-52-71	D40738J	9			D40824J	15			YL951-YL954, YN232-YN235
0186	20		CQ		8-11	31-52-71	D40738J	9			D40824J	15			YL955-YL999, YN236-YR328
0187	16		CQ		6-2	33-11-11	D40924J	4			TB1092V	A005	1		YC051-YD158, YN231
0187	16		CQ		6-8	33-11-11	D40924J	4			TB1092V	A005	1		YL951
0187	16		CQ		6-9	33-11-11	D40924J	4			TB1092V	A005	1		YL952-YL954, YN232-YN235
0187	16		CQ		6-3	33-11-11	D40924J	4			TB1092V	A005	1		YL955-YL999, YN236-YR328
0189	16		PA		5-3	33-11-11	D11810	14			TB1092W	B001	1		YC051-YD158, YN231
0189	16		PA		6-2	33-11-11	D11810	14			TB1092W	B001	1		YL951
0189	16		PA		6-0	33-11-11	D11810	14			TB1092W	B001	1		YL952-YL954, YN232-YN235
0189	16		PA		5-0	33-11-11	D11810	14			TB1092W	B001	1		YL955-YL999, YN236-YR328
0190	14		PA		4-11	33-11-11	D11810	7	14		GD00141	AC..	E		YC051-YD158, YN231
0190	14		PA		4-9	33-11-11	D11810	7	14		GD00141	AC..	E		YL951
0190	14		PA		4-6	33-11-11	D11810	7	14		GD00141	AC..	E		YL952-YL954, YN232-YN235

WIRE LIST
D280A108

91-21-11
Section W0000
Page 14
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)											
0190	14		PA		4-5	33-11-11		D11810	7	14		GD00141	AC..	E		YL955-YL999, YN236-YR328
0191	16		CQ		6-2	33-11-11		D40924J	8			TB1092W	B001	1		YC051-YD158, YN231
0191	16		CQ		6-8	33-11-11		D40924J	8			TB1092W	B001	1		YL951
0191	16		CQ		6-10	33-11-11		D40924J	8			TB1092W	B001	1		YL952-YL954, YN232-YN235
0191	16		CQ		6-3	33-11-11		D40924J	8			TB1092W	B001	1		YL955-YL999, YN236-YR328
0192	16		CQ		6-2	33-11-11		D40924J	10			TB1092W	B001	1		YC051-YD158, YN231
0192	16		CQ		6-8	33-11-11		D40924J	10			TB1092W	B001	1		YL951
0192	16		CQ		6-10	33-11-11		D40924J	10			TB1092W	B001	1		YL952-YL954, YN232-YN235
0192	16		CQ		6-3	33-11-11		D40924J	10			TB1092W	B001	1		YL955-YL999, YN236-YR328
0193	16		PA		4-3	33-11-11		D02650	15			TB1092V	A005	1		YC051-YD158, YN231
0193	16		PA		4-8	33-11-11		D02650	15			TB1092V	A005	1		YL951
0193	16		PA		4-7	33-11-11		D02650	15			TB1092V	A005	1		YL952-YL954, YN232-YN235
0193	16		PA		4-0	33-11-11		D02650	15			TB1092V	A005	1		YL955-YL999, YN236-YR328
0194	14		PA		5-3	33-11-11		D11810	5	14		D02650		19		YC051-YD158, YL951-YR328
0195	14		PA		4-0	33-11-11		D02650	23			GD00141	AC..	E		YC051-YD158, YN231
0195	14		PA		3-11	33-11-11		D02650	23			GD00141	AC..	E		YL951
0195	14		PA		3-8	33-11-11		D02650	23			GD00141	AC..	E		YL952-YL954, YN232-YN235
0195	14		PA		3-6	33-11-11		D02650	23			GD00141	AC..	E		YL955-YL999, YN236-YR328
0196	20		PA		3-0	33-11-11		D00903	1			TB1092W	B001	1		YC051-YD158, YN231
0196	20		PA		2-3	33-11-11		D00903	1			TB1092W	B001	1		YL951
0196	20		PA		2-5	33-11-11		D00903	1			TB1092W	B001	1		YL952-YL954, YN232-YN235
0196	20		PA		2-10	33-11-11		D00903	1			TB1092W	B001	1		YL955-YL999, YN236-YR328
0197	20		PA		3-1	33-11-11		D00903	2			GD1010C	AC..	1A		YC051-YD158, YN231
0197	20		PA		2-9	33-11-11		D00903	2			GD1010C	AC..	1A		YL951-YL954, YN232-YN235
0197	20		PA		2-2	33-11-11		D00903	2			GD1010C	AC..	1A		YL955-YL999, YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W0000

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)										
0201	18		CQ		7-11	33-11-31	D11812	4			D40924J	15	18		YC051-YD158, YN231
0201	18		CQ		7-8	33-11-31	D11812	4			D40924J	15	18		YL951
0201	18		CQ		7-9	33-11-31	D11812	4			D40924J	15	18		YL952-YL999, YN232-YR328
0202	14		PA		4-11	33-11-31	D11812	6	14		GD00141	AC..	E		YC051-YD158, YN231
0202	14		PA		4-10	33-11-31	D11812	6	14		GD00141	AC..	E		YL951
0202	14		PA		4-7	33-11-31	D11812	6	14		GD00141	AC..	E		YL952-YL954, YN232-YN235
0202	14		PA		4-5	33-11-31	D11812	6	14		GD00141	AC..	E		YL955-YL999, YN236-YR328
0203	16		PA		9-4	33-11-31	D11812	2			D00686	4			YC051-YD158
0203	16		PA		7-11	33-11-31	TB1092W	A009	1		D00686	4			YL951
0203	16		PA		8-0	33-11-31	TB1092W	A009	1		D00686	4			YL952-YL954, YN232-YN235
0203	16		PA		7-6	33-11-31	TB1092W	A009	1		D00686	4			YL955-YL999, YN236-YR328
0203	16		PA		7-9	33-11-31	TB1092W	A009	1		D00686	4			YN231
0204	16		PA		7-8	33-11-31	D00686	2			GD1010A	AC..	1		YC051-YD158, YN231
0204	16		PA		7-7	33-11-31	D00686	2			GD1010A	AC..	1		YL951-YL954, YN232-YN235
0204	16		PA		7-9	33-11-31	D00686	2			GD1010A	AC..	1		YL955-YL999, YN236-YR328
0205	16		PA		7-11	33-11-31	D11812	3			D00319	2	16		YC051-YD158, YN231
0205	16		PA		8-1	33-11-31	D11812	3			D00319	2	16		YL951
0205	16		PA		7-7	33-11-31	D11812	3			D00319	2	16		YL952-YL959, YN232-YN235
0206	16		PA		4-11	33-11-31	D00319	1	16		GD1010A	AC..	1		YC051-YD158, YN231
0206	16		PA		5-0	33-11-31	D00319	1	16		GD1010A	AC..	1		YL951-YL954, YN232-YN235
0206	16		PA		5-2	33-11-31	D00319	1	16		GD1010A	AC..	1		YL955-YL959
0207	20		G5		8-6	22-13-11	D00423	29			D04221J	1			YC051-YD158, YN231
0207	20		G5		8-7	22-13-11	D00423	29			D04221J	1			YL951
0207	20		G5		8-4	22-13-11	D00423	29			D04221J	1			YL952-YL999, YN232-YR328
0211	16		PA		5-2	33-11-32	D11810	4			TB1092W	A021	1		YC051-YD158, YN231
0211	16		PA		5-4	33-11-32	D11810	4			TB1092W	A021	1		YL951
0211	16		PA		5-1	33-11-32	D11810	4			TB1092W	A021	1		YL952-YL954, YN232-YN235

WIRE LIST
D280A108

91-21-11
Section W0000
Page 16
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)											
0211	16		PA		4-8	33-11-32	D11810		4			TB1092W	A021	1		YL955-YL999, YN236-YR328
0212	16		PA		5-3	33-11-32	D11810		8			TB1092W	A001	1		YC051-YD158, YN231
0212	16		PA		6-2	33-11-32	D11810		8			TB1092W	A001	1		YL951
0212	16		PA		6-0	33-11-32	D11810		8			TB1092W	A001	1		YL952-YL954, YN232-YN235
0212	16		PA		5-0	33-11-32	D11810		8			TB1092W	A001	1		YL955-YL999, YN236-YR328
0213	16		CQ		5-2	33-11-32	D11810		10			TB1092W	B021	1		YC051-YD158, YN231
0213	16		CQ		5-4	33-11-32	D11810		10			TB1092W	B021	1		YL951
0213	16		CQ		5-1	33-11-32	D11810		10			TB1092W	B021	1		YL952-YL954, YN232-YN235
0213	16		CQ		4-8	33-11-32	D11810		10			TB1092W	B021	1		YL955-YL999, YN236-YR328
0214	20		PA		5-3	33-11-32	D11810		1			TB1092V	A005	1		YC051-YD158, YN231
0214	20		PA		6-1	33-11-32	D11810		1			TB1092V	A005	1		YL951
0214	20		PA		5-5	33-11-32	D11810		1			TB1092V	A005	1		YL952-YL954, YN232-YN235
0214	20		PA		4-11	33-11-32	D11810		1			TB1092V	A005	1		YL955-YL999, YN236-YR328
0215	20		PA		4-11	33-11-32	D11810		2			GD00141	AC..	E		YC051-YD158, YN231
0215	20		PA		4-9	33-11-32	D11810		2			GD00141	AC..	E		YL951
0215	20		PA		4-6	33-11-32	D11810		2			GD00141	AC..	E		YL952-YL954, YN232-YN235
0215	20		PA		4-5	33-11-32	D11810		2			GD00141	AC..	E		YL955-YL999, YN236-YR328
0216	16		CQ		9-10	33-11-32	D11810		12			D11844		4		YC051-YD158, YN231
0216	16		CQ		9-2	33-11-32	D11810		12			D11844		4		YL951
0216	16		CQ		9-3	33-11-32	D11810		12			D11844		4		YL952-YL999, YN232-YR328
0219	20		PA		5-1	33-11-32	D00423		1			TB1092W	A021	1		YC051-YD158, YN231
0219	20		PA		5-2	33-11-32	D00423		1			TB1092W	A021	1		YL951-YL954, YN232-YN235
0219	20		PA		4-9	33-11-32	D00423		1			TB1092W	A021	1		YL955-YL999, YN236-YR328
0220	20		PA		4-11	33-11-32	D00423		2			GD1010C	AC..	1A		YC051-YD158, YN231
0220	20		PA		4-10	33-11-32	D00423		2			GD1010C	AC..	1A		YL951-YL954, YN232-YN235

WIRE LIST

D280A108

91-21-11

Section W0000

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)										
0220	20		PA		5-4	33-11-32	D00423		2		GD1010C	AC..	1A		YL955-YL999, YN236-YR328
0221	20		PA		4-3	33-11-32	D02650		1		TB1092W	A021	1		YC051-YD158, YL952-YL954, YN231-YN235
0221	20		PA		4-5	33-11-32	D02650		1		TB1092W	A021	1		YL951
0221	20		PA		3-9	33-11-32	D02650		1		TB1092W	A021	1		YL955-YL999, YN236-YR328
0222	20		PA		4-1	33-11-32	D02650		2		GD1010C	AC..	1A		YC051-YD158, YL951, YN231
0222	20		PA		3-11	33-11-32	D02650		2		GD1010C	AC..	1A		YL952-YL954, YN232-YN235
0222	20		PA		4-5	33-11-32	D02650		2		GD1010C	AC..	1A		YL955-YL999, YN236-YR328
0223	20		PA		3-0	33-11-32	D00714		1		TB1092V	A007	1		YC051-YD158, YN231
0223	20		PA		2-4	33-11-32	D00714		1		TB1092V	A007	1		YL951
0223	20		PA		2-6	33-11-32	D00714		1		TB1092V	A007	1		YL952-YL954, YN232-YN235
0223	20		PA		2-11	33-11-32	D00714		1		TB1092V	A007	1		YL955-YL999, YN236-YR328
0224	20		PA		3-1	33-11-32	D00714		2		GD1010C	AC..	1A		YC051-YD158, YN231
0224	20		PA		2-11	33-11-32	D00714		2		GD1010C	AC..	1A		YL951-YL954, YN232-YN235
0224	20		PA		2-5	33-11-32	D00714		2		GD1010C	AC..	1A		YL955-YL999, YN236-YR328
0225	20		PA		4-3	33-11-11	D01036		1		TB1092W	B001	1		YC051-YD158, YN231
0225	20		PA		4-8	33-11-11	D01036		1		TB1092W	B001	1		YL951
0225	20		PA		4-7	33-11-11	D01036		1		TB1092W	B001	1		YL952-YL954, YN232-YN235
0225	20		PA		4-0	33-11-11	D01036		1		TB1092W	B001	1		YL955-YL999, YN236-YR328
0226	20		PA		4-1	33-11-11	D01036		2		GD1010C	AC..	1A		YC051-YD158, YN231
0226	20		PA		4-0	33-11-11	D01036		2		GD1010C	AC..	1A		YL951
0226	20		PA		3-10	33-11-11	D01036		2		GD1010C	AC..	1A		YL952-YL954, YN232-YN235
0226	20		PA		4-4	33-11-11	D01036		2		GD1010C	AC..	1A		YL955-YL999, YN236-YR328
0229	20		G5		7-0	33-11-32	D11732		1		TB1092W	B021	1		YC051-YD158, YN231

WIRE LIST

D280A108

91-21-11

Section W0000

Page 18

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001			P1 - CAPTAINS INSTRUMENT PANEL (continued)											
0229	20		G5		7-2	33-11-32	D11732		1		TB1092W	B021	1		YL951-YL954, YN232-YN235
0229	20		G5		6-8	33-11-32	D11732		1		TB1092W	B021	1		YL955-YL999, YN236-YR328
0230	20		G5		6-10	33-11-32	D11732		2		GD1010C	AC..	1A		YC051-YD158, YL951-YL954, YN231-YN235
0230	20		G5		7-4	33-11-32	D11732		2		GD1010C	AC..	1A		YL955-YL999, YN236-YR328
0231	20		PA		6-11	33-11-32	D00339		1		TB1092W	B021	1		YC051-YD158, YN231
0231	20		PA		7-0	33-11-32	D00339		1		TB1092W	B021	1		YL951
0231	20		PA		7-1	33-11-32	D00339		1		TB1092W	B021	1		YL952-YL954, YN232-YN235
0231	20		PA		6-7	33-11-32	D00339		1		TB1092W	B021	1		YL955-YL999, YN236-YR328
0232	20		PA		6-9	33-11-32	D00339		2		GD1010C	AC..	1A		YC051-YD158, YL952-YL954, YN231-YN235
0232	20		PA		6-8	33-11-32	D00339		2		GD1010C	AC..	1A		YL951
0232	20		PA		7-3	33-11-32	D00339		2		GD1010C	AC..	1A		YL955-YL999, YN236-YR328
0233	20		CQ		8-6	33-18-11	D00423		39		D40924J		17		YC051-YD158, YN231
0233	20		CQ		8-8	33-18-11	D00423		39		D40924J		17		YL951
0233	20		CQ		8-5	33-18-11	D00423		39		D40924J		17		YL952-YL999, YN232-YR328
0234	20		CQ		8-6	33-18-11	D00423		37		D40924J		18		YC051-YD158, YN231
0234	20		CQ		8-8	33-18-11	D00423		37		D40924J		18		YL951
0234	20		CQ		8-5	33-18-11	D00423		37		D40924J		18		YL952-YL999, YN232-YR328
0235	20		CQ		5-0	33-18-11	D00423		34		GD1010B	DC..	1A		YC051-YD158, YL952-YL954, YN231-YN235
0235	20		CQ		4-11	33-18-11	D00423		34		GD1010B	DC..	1A		YL951
0235	20		CQ		5-4	33-18-11	D00423		34		GD1010B	DC..	1A		YL955-YL999, YN236-YR328
0236	20		CQ		3-3	33-18-21	D00714		10		TB1092Y	A017	1A		YC051-YD158, YN231
0236	20		CQ		2-8	33-18-21	D00714		10		TB1092Y	A017	1A		YL951
0236	20		CQ		2-9	33-18-21	D00714		10		TB1092Y	A017	1A		YL952-YL954, YN232-YN235

WIRE LIST

D280A108

91-21-11

Section W0000

Page 19

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)										
0236	20		CQ		3-0	33-18-21	D00714	10			TB1092Y	A017	1A		YL955-YL999, YN236-YR328
0237	20		CQ		5-3	33-18-21	D40924J	12			TB3092Y	A011	1A		YC051-YD158, YN231
0237	20		CQ		5-5	33-18-21	D40924J	12			TB3092Y	A011	1A		YL951
0237	20		CQ		6-3	33-18-21	D40924J	12			TB3092Y	A011	1A		YL952-YL954, YN232-YN235
0237	20		CQ		5-2	33-18-21	D40924J	12			TB3092Y	A011	1A		YL955-YL999, YN236-YR328
0239	20		CQ		6-1	33-18-21	D40924J	9			TB1092Y	A017	1A		YC051-YD158, YN231
0239	20		CQ		6-5	33-18-21	D40924J	9			TB1092Y	A017	1A		YL951
0239	20		CQ		6-6	33-18-21	D40924J	9			TB1092Y	A017	1A		YL952-YL954, YN232-YN235
0239	20		CQ		6-0	33-18-21	D40924J	9			TB1092Y	A017	1A		YL955-YL999, YN236-YR328
0241	20		CQ		6-1	33-18-21	D40924J	13			TB1092Y	B017	1A		YC051-YD158, YN231
0241	20		CQ		6-5	33-18-21	D40924J	13			TB1092Y	B017	1A		YL951
0241	20		CQ		6-6	33-18-21	D40924J	13			TB1092Y	B017	1A		YL952-YL954, YN232-YN235
0241	20		CQ		6-0	33-18-21	D40924J	13			TB1092Y	B017	1A		YL955-YL999, YN236-YR328
0242	20		G5		8-11	33-18-21	D00423	28			D40824J	22			YC051-YD158, YN231
0242	20		G5		9-1	33-18-21	D00423	28			D40824J	22			YL951
0242	20		G5		8-10	33-18-21	D00423	28			D40824J	22			YL952-YL999, YN232-YR328
0244	20		CQ		7-7	33-18-23	D00339	6			TB3092Z	A021	1A		YC051-YD158, YL955-YN231, YN236-YR328
0244	20		CQ		7-11	33-18-23	D00339	6			TB3092Z	A021	1A		YL951
0244	20		CQ		8-1	33-18-23	D00339	6			TB3092Z	A021	1A		YL952-YL954, YN232-YN235
0245	20		CQ		6-10	33-18-23	D00339	7			GD1010B	DC..	1A		YC051-YD158, YL951-YL954, YN231-YN235
0245	20		CQ		7-2	33-18-23	D00339	7			GD1010B	DC..	1A		YL955-YL999, YN236-YR328
0246	20		CQ		7-6	33-18-23	D00339	4			TB3092Y	A011	1A		YC051-YD158, YN231
0246	20		CQ		7-8	33-18-23	D00339	4			TB3092Y	A011	1A		YL951
0246	20		CQ		7-11	33-18-23	D00339	4			TB3092Y	A011	1A		YL952-YL954, YN232-YN235

WIRE LIST
D280A108

91-21-11
Section W0000
Page 20
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)										
0246	20		CQ		7-4	33-18-23	D00339		4		TB3092Y	A011	1A		YL955-YL999, YN236-YR328
0247	20		CQ		7-7	33-18-23	D00339		3		TB3092Y	A015	1A		YC051-YD158, YN231
0247	20		CQ		7-11	33-18-23	D00339		3		TB3092Y	A015	1A		YL951-YL954, YN232-YN235
0247	20		CQ		7-5	33-18-23	D00339		3		TB3092Y	A015	1A		YL955-YL999, YN236-YR328
0249	20		CQ		9-2	33-18-51	D40738J		21		TB3092Y	B017	1A		YC051-YD158, YN231
0249	20		CQ		8-10	33-18-51	D40738J		21		TB3092Y	B017	1A		YL951
0249	20		CQ		9-0	33-18-51	D40738J		21		TB3092Y	B017	1A		YL952-YL954, YN232-YN235
0249	20		CQ		8-6	33-18-51	D40738J		21		TB3092Y	B017	1A		YL955-YL999, YN236-YR328
0250	20		CQ		8-6	33-18-62	D00423		38		D40924J		19		YC051-YD158, YN231
0250	20		CQ		8-8	33-18-62	D00423		38		D40924J		19		YL951
0250	20		CQ		8-5	33-18-62	D00423		38		D40924J		19		YL952-YL999, YN232-YR328
0251	20		CQ		8-6	33-18-62	D00423		36		D40924J		20		YC051-YD158, YN231
0251	20		CQ		8-8	33-18-62	D00423		36		D40924J		20		YL951
0251	20		CQ		8-5	33-18-62	D00423		36		D40924J		20		YL952-YL999, YN232-YR328
0252	24		B6		7-4	27-81-31	D00339		14		D04221J		15		YC051-YD158, YL951-YR328
0253	24		B6		7-4	27-81-31	D00339		15		D04221J		16		YC051-YD158, YL951-YR328
0254	22		PA		7-8	29-23-11	D00903		5		D40578J		3		YC051-YD158, YN231
0254	22		PA		7-4	29-23-11	D00903		5		D40578J		3		YL951-YL954, YN232-YN235
0254	22		PA		7-2	29-23-11	D00903		5		D40578J		3		YL955-YL999, YN236-YR328
0255	22		PA		7-0	29-23-11	D00903		6		GD0201B	DC..	1A		YC051-YD158, YN231
0255	22		PA		6-6	29-23-11	D00903		6		GD0201B	DC..	1A		YL951
0255	22		PA		6-5	29-23-11	D00903		6		GD0201B	DC..	1A		YL952-YL954, YN232-YN235
0255	22		PA		6-4	29-23-11	D00903		6		GD0201B	DC..	1A		YL955-YL999, YN236-YR328
0256	16		PA		5-3	33-11-32	D11810		6		TB1092V	A007	1		YC051-YD158, YN231
0256	16		PA		6-1	33-11-32	D11810		6		TB1092V	A007	1		YL951

WIRE LIST

D280A108

91-21-11

Section W0000

Page 21

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)										
0256	16		PA		5-5	33-11-32	D11810		6		TB1092V	A007	1		YL952-YL954, YN232-YN235
0256	16		PA		4-11	33-11-32	D11810		6		TB1092V	A007	1		YL955-YL999, YN236-YR328
0261	20		CQ		7-5	33-14-11	D46033J		13		D01036		10		YC051-YD158, YN231
0261	20		CQ		7-2	33-14-11	D46033J		13		D01036		10		YL951
0261	20		CQ		7-3	33-14-11	D46033J		13		D01036		10		YL952-YL999, YN232-YR328
0262	20		G5		6-7	33-14-11	D46033J		8		TB1092Y	B019	1A		YC051-YD158, YN231
0262	20		G5		6-11	33-14-11	D46033J		8		TB1092Y	B019	1A		YL951
0262	20		G5		7-0	33-14-11	D46033J		8		TB1092Y	B019	1A		YL952-YL954, YN232-YN235
0262	20		G5		6-6	33-14-11	D46033J		8		TB1092Y	B019	1A		YL955-YL999, YN236-YR328
0263	20		G5		4-2	33-14-11	D01036		6		TB1092Y	B019	1A		YC051-YD158, YN231
0263	20		G5		4-5	33-14-11	D01036		6		TB1092Y	B019	1A		YL951
0263	20		G5		4-3	33-14-11	D01036		6		TB1092Y	B019	1A		YL952-YL954, YN232-YN235
0263	20		G5		3-9	33-14-11	D01036		6		TB1092Y	B019	1A		YL955-YL999, YN236-YR328
0264	20		G5		5-0	33-14-11	D40944J		3		TB1092Y	B019	1A		YC051-YD158, YN231
0264	20		G5		5-3	33-14-11	D40944J		3		TB1092Y	B019	1A		YL951
0264	20		G5		5-4	33-14-11	D40944J		3		TB1092Y	B019	1A		YL952-YL954, YN232-YN235
0264	20		G5		4-10	33-14-11	D40944J		3		TB1092Y	B019	1A		YL955-YL999, YN236-YR328
0265	20		G5		4-2	33-14-11	D01036		3		GD1010B	AC..	1A		YC051-YD158, YL951, YN231
0265	20		G5		3-11	33-14-11	D01036		3		GD1010B	AC..	1A		YL952-YL954, YN232-YN235
0265	20		G5		4-3	33-14-11	D01036		3		GD1010B	AC..	1A		YL955-YL999, YN236-YR328
0266	20		G5		6-4	33-14-11	D40944J		4		D01036		12		YC051-YD158, YN231
0266	20		G5		6-0	33-14-11	D40944J		4		D01036		12		YL951
0266	20		G5		6-1	33-14-11	D40944J		4		D01036		12		YL952-YL999, YN232-YR328
0267	20		G5		6-4	33-14-11	D40944J		5		D01036		4		YC051-YD158, YN231
0267	20		G5		6-0	33-14-11	D40944J		5		D01036		4		YL951

WIRE LIST

D280A108

91-21-11

Section W0000

Page 22

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)										
0267	20		G5		6-1	33-14-11	D40944J		5		D01036		4		YL952-YL999, YN232-YR328
0268	20		G5		6-4	33-14-11	D40944J		6		D01036		5		YC051-YD158, YN231
0268	20		G5		6-0	33-14-11	D40944J		6		D01036		5		YL951
0268	20		G5		6-1	33-14-11	D40944J		6		D01036		5		YL952-YL999, YN232-YR328
0269	20		G5		8-5	33-14-11	D40944J		12		D40738J		37		YC051-YD158, YN231
0269	20		G5		7-10	33-14-11	D40944J		12		D40738J		37		YL951-YL999, YN232-YR328
0270	20		G5		8-5	33-14-11	D40944J		11		D40738J		36		YC051-YD158, YN231
0270	20		G5		7-10	33-14-11	D40944J		11		D40738J		36		YL951-YL999, YN232-YR328
0271	20		G5		8-5	33-14-11	D40944J		17		D40738J		39		YC051-YD158, YN231
0271	20		G5		7-10	33-14-11	D40944J		17		D40738J		39		YL951-YL999, YN232-YR328
0272	20		G5		8-5	33-14-11	D40944J		16		D40738J		38		YC051-YD158, YN231
0272	20		G5		7-10	33-14-11	D40944J		16		D40738J		38		YL951-YL999, YN232-YR328
0273	20		G5		6-4	33-14-11	D40944J		7		D01036		11		YC051-YD158, YN231
0273	20		G5		6-0	33-14-11	D40944J		7		D01036		11		YL951
0273	20		G5		6-1	33-14-11	D40944J		7		D01036		11		YL952-YL999, YN232-YR328
0274	20		G5		6-4	33-14-11	D40944J		8		D01036		9		YC051-YD158, YN231
0274	20		G5		6-0	33-14-11	D40944J		8		D01036		9		YL951
0274	20		G5		6-1	33-14-11	D40944J		8		D01036		9		YL952-YL999, YN232-YR328
0275	20		G5		6-4	33-14-11	D40944J		9		D01036		8		YC051-YD158, YN231
0275	20		G5		6-0	33-14-11	D40944J		9		D01036		8		YL951
0275	20		G5		6-1	33-14-11	D40944J		9		D01036		8		YL952-YL999, YN232-YR328
0276	20		G5		6-4	33-14-11	D40944J		10		D01036		7		YC051-YD158, YN231
0276	20		G5		6-0	33-14-11	D40944J		10		D01036		7		YL951
0276	20		G5		6-1	33-14-11	D40944J		10		D01036		7		YL952-YL999, YN232-YR328
0277	20		G5		9-0	33-14-11	D40944J		18		D40740J		36		YC051-YD158, YN231
0277	20		G5		8-6	33-14-11	D40944J		18		D40740J		36		YL951, YL955-YL999, YN236-YR328
0277	20		G5		8-5	33-14-11	D40944J		18		D40740J		36		YL952-YL954, YN232-YN235

WIRE LIST

D280A108

91-21-11

Section W0000

Page 23

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)										
0278	20		G5		9-0	33-14-11	D40944J	20			D40740J	38			YC051-YD158, YN231
0278	20		G5		8-6	33-14-11	D40944J	20			D40740J	38			YL951, YL955-YL999, YN236-YR328
0278	20		G5		8-5	33-14-11	D40944J	20			D40740J	38			YL952-YL954, YN232-YN235
0279	20		G5		9-0	33-14-11	D40944J	21			D40740J	39			YC051-YD158, YN231
0279	20		G5		8-6	33-14-11	D40944J	21			D40740J	39			YL951, YL955-YL999, YN236-YR328
0279	20		G5		8-5	33-14-11	D40944J	21			D40740J	39			YL952-YL954, YN232-YN235
0280	20		G5		9-0	33-14-11	D40944J	19			D40740J	37			YC051-YD158, YN231
0280	20		G5		8-6	33-14-11	D40944J	19			D40740J	37			YL951, YL955-YL999, YN236-YR328
0280	20		G5		8-5	33-14-11	D40944J	19			D40740J	37			YL952-YL954, YN232-YN235
0281	18		CQ		1-6	31-62-11	D03993	4	18		GD00701	DC..	E		YC051-YD158
0281	18		CQ		0-12	31-62-11	D03993	4	18		GD00701	DC..	E		YL951-YR328
0290	16		CQ		9-10	33-11-32	D11810	11			D11844	3			YC051-YD158, YN231
0290	16		CQ		9-2	33-11-32	D11810	11			D11844	3			YL951
0290	16		CQ		9-3	33-11-32	D11810	11			D11844	3			YL952-YL999, YN232-YR328
0291	16		CQ		6-2	33-11-32	D40924J	6			TB1092V	A007	1		YC051-YD158, YN231
0291	16		CQ		6-8	33-11-32	D40924J	6			TB1092V	A007	1		YL951
0291	16		CQ		6-9	33-11-32	D40924J	6			TB1092V	A007	1		YL952-YL954, YN232-YN235
0291	16		CQ		6-3	33-11-32	D40924J	6			TB1092V	A007	1		YL955-YL999, YN236-YR328
0301	22		PA		6-10	32-64-11	D11990	1			GD0201B	DC..	1A		YC051-YD158, YN231
0301	22		PA		6-9	32-64-11	D11990	1			GD0201B	DC..	1A		YL951
0301	22		PA		6-8	32-64-11	D11990	1			GD0201B	DC..	1A		YL952-YL999, YN232-YR328
0302	24		PK		6-11	32-64-11	D11990	2			TB0201Z	A001	1A		YC051-YD158, YL951, YN231
0302	24		PK		6-10	32-64-11	D11990	2			TB0201Z	A001	1A		YL952-YL999, YN232-YR328
0303	24		PK		7-7	32-64-11	D11990	3			D40578J	1			YC051-YD158, YL951-YL959, YN231-YN235

WIRE LIST

D280A108

91-21-11
Section W0000
Page 24
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001			P1 - CAPTAINS INSTRUMENT PANEL (continued)											
0303	24		PK		6-10	32-64-11	D11990		3		TB0201Y	A009	1A		YL963-YL999, YN236-YR328
0304	24		G6		6-11	33-25-11	D11990		4		TB0201Y	A005	1A		YC051-YD158, YN231
0304	24		G6		6-10	33-25-11	D11990		4		TB0201Y	A005	1A		YL951-YL999, YN232-YR328
0306	22		PA		6-10	32-64-11	D11990		6		GD0201B	DC..	1A		YC051-YD158, YN231
0306	22		PA		6-9	32-64-11	D11990		6		GD0201B	DC..	1A		YL951
0306	22		PA		6-8	32-64-11	D11990		6		GD0201B	DC..	1A		YL952-YL999, YN232-YR328
0308	24		PK		7-9	32-31-11	D11990		8		D04221J		38		YC051-YD158, YN231
0308	24		PK		7-8	32-31-11	D11990		8		D04221J		38		YL951-YL999, YN232-YR328
0309	24		B6		6-9	32-31-11	D11990		9		D40924J		31		YC051-YD158, YL951-YR328
0311	22		G5		6-10	32-41-11	D11990		11		GD0201B	DC..	1A		YC051-YD158, YN231
0311	22		G5		6-9	32-41-11	D11990		11		GD0201B	DC..	1A		YL951
0311	22		G5		6-8	32-41-11	D11990		11		GD0201B	DC..	1A		YL952-YL999, YN232-YR328
0313	24		G6		7-7	32-41-11	D11990		13		D40914J		13		YC051-YD158, YN231
0313	24		G6		7-6	32-41-11	D11990		13		D40914J		13		YL951-YL999, YN232-YR328
0314	22		G5		6-10	32-41-11	D11990		14		GD0201B	DC..	1A		YC051-YD158, YN231
0314	22		G5		6-9	32-41-11	D11990		14		GD0201B	DC..	1A		YL951
0314	22		G5		6-8	32-41-11	D11990		14		GD0201B	DC..	1A		YL952-YL999, YN232-YR328
0315	24		G6		5-0	33-25-11	D40804J		1		TB0201Y	A005	1A		YC051-YD158, YL951-YR328
0316	24		G6		7-7	32-41-11	D11990		16		D40914J		12		YC051-YD158, YN231
0316	24		G6		7-6	32-41-11	D11990		16		D40914J		12		YL951-YL999, YN232-YR328
0324	16		PA		6-1	33-11-31	D11812		2		TB1092W	A009	1		YL951
0324	16		PA		5-5	33-11-31	D11812		2		TB1092W	A009	1		YL952-YL954, YN232-YN235
0324	16		PA		4-11	33-11-31	D11812		2		TB1092W	A009	1		YL955-YL999, YN236-YR328
0324	16		PA		5-3	33-11-31	D11812		2		TB1092W	A009	1		YN231
0325	20		PA		3-7	33-11-31	TB1092W	A009	1		D40738J		17		YL951
0325	20		PA		3-9	33-11-31	TB1092W	A009	1		D40738J		17		YL952-YL954, YN232-YN235

WIRE LIST

D280A108

91-21-11

Section W0000

Page 25

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)										
0325	20		PA		5-0	33-11-31	TB1092W	A009	1		D40738J	17			YL955-YL999, YN236-YR328
0325	20		PA		4-1	33-11-31	TB1092W	A009	1		D40738J	17			YN231
0326	20		PA		3-10	33-11-31	D40738J		18		GD1010A	AC..	1		YL951-YL954, YN232-YN235
0326	20		PA		5-3	33-11-31	D40738J		18		GD1010A	AC..	1		YL955-YL999, YN236-YR328
0326	20		PA		4-0	33-11-31	D40738J		18		GD1010A	AC..	1		YN231
0327	22		PA		4-10	23-32-12	D40578J		15		TB0201Y	A005	1A		YC051-YD157
0328	22		PA		4-10	34-41-11	D40578J		17		TB0201Z	A001	1A		YC053-YD158, YN231
0328	22		PA		4-11	34-41-11	D40578J		17		TB0201Z	A001	1A		YL951
0328	22		PA		5-0	34-41-11	D40578J		17		TB0201Z	A001	1A		YL952-YL999, YN232-YR328
0330	24		PK		8-4	23-51-11	D04221J		31		D40738J	19			YL951-YL999, YN232-YR328
0330	24		PK		8-11	23-51-11	D04221J		31		D40738J	19			YN231
0331	24		PK		8-4	23-51-11	D04221J		32		D40738J	20			YL951-YL999, YN232-YR328
0331	24		PK		8-11	23-51-11	D04221J		32		D40738J	20			YN231
0341	20		CQ		3-0	31-22-11	D00714		4		GD1010B	DC..	1A		YC054-YD158, YL951-YL954, YN231-YN235
0341	20		CQ		2-4	31-22-11	D00714		4		GD1010B	DC..	1A		YL955-YL999, YN236-YR328
0363	24		PK		4-11	32-64-11	D40578J		1		TB0201Y	A009	1A		YL963-YL999, YN236-YR328
1001	16		X1	YA	6-0	31-62-11	D03977B		59		D41833J	7			YC051-YD158, YN231
1001	16		X1	YA	6-4	31-62-11	D03977B		59		D41833J	7			YL951-YL954, YN232-YN235
1001	16		X1	YA	6-3	31-62-11	D03977B		59		D41833J	7			YL955-YL999, YN236-YR328
1001Z				YA	0-0	31-62-11	D03977B	PERG	1A		D41833J	S/R			YC051-YD158, YL951-YR328
1002	16		N1	YB	5-2	31-62-11	D03979B		59		D41823J	4			YC051-YC052
1002	16		X1	YB	5-2	31-62-11	D03979B		59		D41833J	10			YC053-YD158, YL951-YR328
1002Z				YB	0-0	31-62-11	D03979B	PERG	1A		D41823J	S/R			YC051-YC052
1002Z				YB	0-0	31-62-11	D03979B	PERG	1A		D41833J	S/R			YC053-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0000

Page 26

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W0001	286A0001	P1 - CAPTAINS INSTRUMENT PANEL (continued)													
1003	16	X1	YC	5-0	31-62-11	D03981B	59		D41833J	4			YC051-YD158, YN231		
1003	16	X1	YC	4-11	31-62-11	D03981B	59		D41833J	4			YL951-YL999, YN232-YR328		
1003Z			YC	0-0	31-62-11	D03981B	PERG	1A	D41833J	S/R			YC051-YD158, YL951-YR328		
1004	22	X1	YD	8-5	31-62-11	D03993	3		D41833J	1			YC051-YD158, YN231		
1004	22	X1	YD	8-3	31-62-11	D03993	3		D41833J	1			YL951		
1004	22	X1	YD	8-1	31-62-11	D03993	3		D41833J	1			YL952-YL999, YN232-YR328		
1004Z			YD	0-0	31-62-11	D03993	S/R		D41833J	S/R			YC051-YD158, YL951-YR328		
1005	24	Y1	YE	9-0	31-62-13	D00331	38		D03993	49			YC051-YD158, YN231		
1005	24	Y1	YE	8-10	31-62-13	D00331	38		D03993	49			YL951		
1005	24	Y1	YE	8-7	31-62-13	D00331	38		D03993	49			YL952-YL999, YN232-YR328		
1005Z			YE	0-0	31-62-13	D00331	S/R		D03993	S/R			YC051-YD158, YL951-YR328		
1006	24	Y1	YF	9-0	31-62-13	D00331	39		D03993	37			YC051-YD158, YN231		
1006	24	Y1	YF	8-10	31-62-13	D00331	39		D03993	37			YL951		
1006	24	Y1	YF	8-7	31-62-13	D00331	39		D03993	37			YL952-YL999, YN232-YR328		
1006Z			YF	0-0	31-62-13	D00331	S/R		D03993	S/R			YC051-YD158, YL951-YR328		
1007	24	Y1	YG	9-0	31-62-13	D00331	40		D03993	11			YC051-YD158, YN231		
1007	24	Y1	YG	8-10	31-62-13	D00331	40		D03993	11			YL951		
1007	24	Y1	YG	8-7	31-62-13	D00331	40		D03993	11			YL952-YL999, YN232-YR328		
1007Z			YG	0-0	31-62-13	D00331	S/R		D03993	S/R			YC051-YD158, YL951-YR328		
1008	24	Y1	YH	9-0	31-62-13	D00331	41		D03993	16			YC051-YD158, YN231		
1008	24	Y1	YH	8-10	31-62-13	D00331	41		D03993	16			YL951		
1008	24	Y1	YH	8-7	31-62-13	D00331	41		D03993	16			YL952-YL999, YN232-YR328		
1008Z			YH	0-0	31-62-13	D00331	S/R		D03993	S/R			YC051-YD158, YL951-YR328		
1009	20	X1	YI	5-0	33-11-32	D03993	1		TB1092W	A001	1		YC051-YD158, YN231		
1009	20	X1	YI	5-2	33-11-32	D03993	1		TB1092W	A001	1		YL951		
1009	20	X1	YI	5-3	33-11-32	D03993	1		TB1092W	A001	1		YL952-YL954, YN232-YN235		

WIRE LIST

D280A108

91-21-11

Section W0000

Page 27

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)										
1009	20	X1	YI		4-9	33-11-32	D03993		1		TB1092W	A001	1		YL955-YL999, YN236-YR328
1009Z			YI		0-0	33-11-32	D03993		S/R		GD1010C	ST..	1A		YC051-YC052
1009Z			YI		0-0	33-11-32	D03993		S/R		GD1010B	ST..	1A		YC053-YD158, YN231
1009Z			YI		0-0	33-11-32	D03993		S/R		GB00101	ST..	1A		YL951-YL999, YN232-YR328
1010	20	X1	YJ		4-9	33-11-32	D03993		2		GD1010C	AC..	1A		YC051-YD158, YN231
1010	20	X1	YJ		4-6	33-11-32	D03993		2		GD1010C	AC..	1A		YL951
1010	20	X1	YJ		4-7	33-11-32	D03993		2		GD1010C	AC..	1A		YL952-YL954, YN232-YN235
1010	20	X1	YJ		5-1	33-11-32	D03993		2		GD1010C	AC..	1A		YL955-YL999, YN236-YR328
1010Z			YJ		0-0	33-11-32	D03993		S/R		GD1010C	ST..	1A		YC051-YD158, YL951-YR328
1012R	22	X5	YL		6-1	26-11-21	D40804J		2		TB0101Y	B019	1A		YC051-YD158, YN231
1012R	22	X5	YL		6-3	26-11-21	D40804J		2		TB0101Y	B019	1A		YL951
1012R	22	X5	YL		6-4	26-11-21	D40804J		2		TB0101Y	B019	1A		YL952-YL954, YN232-YN235
1012R	22	X5	YL		5-4	26-11-21	D40804J		2		TB0101Y	B019	1A		YL955-YL999, YN236-YR328
1012Z			YL		0-0	26-11-21	D40804J		DED		TB0101Y	DED			YC051-YD158, YL951-YR328
1013R	22	X5	YM		6-2	26-11-21	D40804J		3		TB0101Z	B021	1A		YC051-YD158, YL951, YN231
1013R	22	X5	YM		6-3	26-11-21	D40804J		3		TB0101Z	B021	1A		YL952-YL954, YN232-YN235
1013R	22	X5	YM		5-4	26-11-21	D40804J		3		TB0101Z	B021	1A		YL955-YL999, YN236-YR328
1013Z			YM		0-0	26-11-21	D40804J		DED		TB0101Z	DED			YC051-YD158, YL951-YR328
1014R	22	X5	YN		4-5	26-11-21	D40738J		14		TB0101Y	B019	1A		YC051-YD158, YN231
1014R	22	X5	YN		3-3	26-11-21	D40738J		14		TB0101Y	B019	1A		YL951
1014R	22	X5	YN		3-6	26-11-21	D40738J		14		TB0101Y	B019	1A		YL952-YL954, YN232-YN235
1014R	22	X5	YN		4-10	26-11-21	D40738J		14		TB0101Y	B019	1A		YL955-YL999, YN236-YR328
1014Z			YN		0-0	26-11-21	D40738J		DED		TB0101Y	DED			YC051-YD158, YL951-YR328
1015R	22	X5	YO		4-5	26-11-21	D40738J		15		TB0101Z	B021	1A		YC051-YD158, YN231

WIRE LIST
D280A108

91-21-11
Section W0000
Page 28
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From			To			Effectivity		
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W0001	286A0001			P1 - CAPTAINS INSTRUMENT PANEL (continued)										
1015R	22	X5	YO	3-3	26-11-21	D40738J	15		TB0101Z	B021	1A		YL951	
1015R	22	X5	YO	3-5	26-11-21	D40738J	15		TB0101Z	B021	1A		YL952-YL954, YN232-YN235	
1015R	22	X5	YO	4-10	26-11-21	D40738J	15		TB0101Z	B021	1A		YL955-YL999, YN236-YR328	
1015Z			YO	0-0	26-11-21	D40738J	DED		TB0101Z	DED			YC051-YD158, YL951-YR328	
1016R	22	X5	YP	4-5	26-11-21	D40738J	16		TB0101Z	B021	1A		YC051-YD158, YN231	
1016R	22	X5	YP	3-3	26-11-21	D40738J	16		TB0101Z	B021	1A		YL951	
1016R	22	X5	YP	3-5	26-11-21	D40738J	16		TB0101Z	B021	1A		YL952-YL954, YN232-YN235	
1016R	22	X5	YP	4-10	26-11-21	D40738J	16		TB0101Z	B021	1A		YL955-YL999, YN236-YR328	
1016Z			YP	0-0	26-11-21	D40738J	DED		TB0101Z	DED			YC051-YD158, YL951-YR328	
101CO			ZA	0-0	31-62-12	D03985A	= 1T		D10031	= C1			YC051-YD158, YL951-YR328	
101CX		0F	ZA	4-9	31-62-12	D03985A	1T		D10031	= A1			YC051-YD158, YN231	
101CX		0F	ZA	4-6	31-62-12	D03985A	1T		D10031	= A1			YL951	
101CX		0F	ZA	4-8	31-62-12	D03985A	1T		D10031	= A1			YL952-YL999, YN232-YR328	
102CO			ZB	0-0	31-62-12	D03987A	= 1T		D10033	= C1			YC051-YD158, YL951-YR328	
102CX		0F	ZB	4-1	31-62-12	D03987A	1T		D10033	= A1			YC051-YD158, YN231	
102CX		0F	ZB	3-11	31-62-12	D03987A	1T		D10033	= A1			YL951	
102CX		0F	ZB	4-0	31-62-12	D03987A	1T		D10033	= A1			YL952-YL999, YN232-YR328	
103CO			ZC	0-0	31-62-12	D03983A	= 1T		D10035	= C1			YC051-YD158, YL951-YR328	
103CX		0F	ZC	4-7	31-62-12	D03983A	1T		D10035	= A1			YC051-YD158, YN231	
103CX		0F	ZC	4-5	31-62-12	D03983A	1T		D10035	= A1			YL951-YL999, YN232-YR328	
104CO			ZD	0-0	31-62-12	D03981A	= 1T		D10037	= C1			YC051-YD158, YL951-YR328	
104CX		0F	ZD	3-8	31-62-12	D03981A	1T		D10037	= A1			YC051-YD158, YN231	
104CX		0F	ZD	3-2	31-62-12	D03981A	1T		D10037	= A1			YL951	
104CX		0F	ZD	3-1	31-62-12	D03981A	1T		D10037	= A1			YL952-YL999, YN232-YR328	

WIRE LIST

D280A108

91-21-11

Section W0000

Page 29

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)										
105CO				ZE	0-0	31-62-12	D03979A	=	1T		D10039	=	C1		YC051-YD158, YL951-YR328
105CX			0F	ZE	3-1	31-62-12	D03979A		1T		D10039	=	A1		YC051-YD158, YN231
105CX			0F	ZE	2-10	31-62-12	D03979A		1T		D10039	=	A1		YL951
105CX			0F	ZE	2-9	31-62-12	D03979A		1T		D10039	=	A1		YL952-YL999, YN232-YR328
106CO				ZF	0-0	31-62-12	D03977A	=	1T		D10041	=	C1		YC051-YD158, YL951-YR328
106CX			0F	ZF	3-7	31-62-12	D03977A		1T		D10041	=	A1		YC051-YD158, YN231
106CX			0F	ZF	3-6	31-62-12	D03977A		1T		D10041	=	A1		YL951
106CX			0F	ZF	3-4	31-62-12	D03977A		1T		D10041	=	A1		YL952-YL999, YN232-YR328
2001B	24		Y2	AA	2-8	31-62-11	D03977B		E04		TB0101Y	B011	1A		YC051-YD158, YN231
2001B	24		Y2	AA	3-1	31-62-11	D03977B		E04		TB0101Y	B011	1A		YL951-YL954, YN232-YN235
2001B	24		Y2	AA	2-6	31-62-11	D03977B		E04		TB0101Y	B011	1A		YL955-YL999, YN236-YR328
2001R	24		Y2	AA	0-0	31-62-11	D03977B		E03		TB0101Y	A011	1A		YC051-YD158, YL951-YR328
2001Z				AA	0-0	31-62-11	D03977B	PERG	1A		GB00101	ST..	1A		YC051-YD158, YL951-YR328
2002B	24		Y2	AB	4-9	31-62-12	D03981B		A04		D04207J		2		YC051-YD158, YN231
2002B	24		Y2	AB	4-8	31-62-12	D03981B		A04		D04207J		2		YL951-YL999, YN232-YR328
2002R	24		Y2	AB	0-0	31-62-12	D03981B		A03		D04207J		1		YC051-YD158, YL951-YR328
2002Z				AB	0-0	31-62-12	D03981B	PERG	1A		D04207J	S/R			YC051-YD158, YL951-YR328
2003B	24		Y2	AC	5-2	31-62-12	D03977B		A04		D04207J		4		YC051-YD158, YN231
2003B	24		Y2	AC	6-1	31-62-12	D03977B		A04		D04207J		4		YL951-YL954, YN232-YN235
2003B	24		Y2	AC	6-0	31-62-12	D03977B		A04		D04207J		4		YL955-YL999, YN236-YR328
2003R	24		Y2	AC	0-0	31-62-12	D03977B		A03		D04207J		3		YC051-YD158, YL951-YR328
2003Z				AC	0-0	31-62-12	D03977B	PERG	1A		D04207J	S/R			YC051-YD158, YL951-YR328
2004B	24		Y2	AD	5-2	31-62-12	D03979B		A04		D04221J		40		YC051-YD158, YN231

WIRE LIST

D280A108

91-21-11

Section W0000

Page 30

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W0001	286A0001			P1 - CAPTAINS INSTRUMENT PANEL (continued)										
2004B	24	Y2	AD	5-1	31-62-12	D03979B	A04			D04221J	40			YL951-YL999, YN232-YR328
2004R	24	Y2	AD	0-0	31-62-12	D03979B	A03			D04221J	39			YC051-YD158, YL951-YR328
2004Z			AD	0-0	31-62-12	D03979B	PERG	1A		D04221J	S/R			YC051-YD158, YL951-YR328
2005B	24	Y2	AE	5-0	31-62-13	D03993	36			TB0101Y	B001	1A		YC051-YD158, YN231
2005B	24	Y2	AE	5-1	31-62-13	D03993	36			TB0101Y	B001	1A		YL951
2005B	24	Y2	AE	5-3	31-62-13	D03993	36			TB0101Y	B001	1A		YL952-YL954, YN232-YN235
2005B	24	Y2	AE	4-9	31-62-13	D03993	36			TB0101Y	B001	1A		YL955-YL999, YN236-YR328
2005R	24	Y2	AE	0-0	31-62-13	D03993	35			TB0101Y	A001	1A		YC051-YD158, YL951-YR328
2005Z			AE	0-0	31-62-13	D03993	S/R			GB00101	ST..	1A		YC051-YD158, YL951-YR328
2006B	24	Y2	AF	5-5	31-62-13	D04207J	10			TB0101Y	B001	1A		YC051-YD158, YL955-YN231, YN236-YR328
2006B	24	Y2	AF	6-4	31-62-13	D04207J	10			TB0101Y	B001	1A		YL951
2006B	24	Y2	AF	6-6	31-62-13	D04207J	10			TB0101Y	B001	1A		YL952-YL954, YN232-YN235
2006R	24	Y2	AF	0-0	31-62-13	D04207J	9			TB0101Y	A001	1A		YC051-YD158, YL951-YR328
2006Z			AF	0-0	31-62-13	D04207J	S/R			GB00101	ST..	1A		YC051-YD158, YL951-YR328
2007B	24	Y2	AG	5-5	31-62-13	D04207J	12			TB0101Y	B001	1A		YC051-YC052
2007R	24	Y2	AG	0-0	31-62-13	D04207J	11			TB0101Y	A001	1A		YC051-YC052
2007Z			AG	0-0	31-62-13	D04207J	S/R			GB00101	ST..	1A		YC051-YC052
2008B	22	X2	AH	8-1	22-23-12	D00319	5			D04207J	18			YC051-YD158, YN231
2008B	22	X2	AH	8-3	22-23-12	D00319	5			D04207J	18			YL951
2008B	22	X2	AH	8-0	22-23-12	D00319	5			D04207J	18			YL952-YL959, YN232-YN235
2008R	22	X2	AH	0-0	22-23-12	D00319	6			D04207J	17			YC051-YD158, YL951-YL959, YN231-YN235
2008Z			AH	0-0	22-23-12	D00319	DED			D04207J	S/R			YC051-YD158, YL951-YL959, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W0000

Page 31

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)										
2009B	24	Y2	AI		7-10	31-22-11	D00714	23			D04221J	34			YC051-YD158, YN231
2009B	24	Y2	AI		7-7	31-22-11	D00714	23			D04221J	34			YL951-YL954, YN232-YN235
2009B	24	Y2	AI		7-6	31-22-11	D00714	23			D04221J	34			YL955-YL999, YN236-YR328
2009R	24	Y2	AI		0-0	31-22-11	D00714	24			D04221J	33			YC051-YD158, YL951-YR328
2009Z			AI		0-0	31-22-11	D00714	DED			D04221J	S/R			YC051-YC052
2009Z			AI		0-0	31-22-11	D00714	S/R			D04221J	S/R			YC053-YD158, YL951-YR328
2010B	24	Y2	AJ		4-2	31-62-11	D40738J	26			TB0101Y	B011	1A		YC051-YD158, YN231
2010B	24	Y2	AJ		3-6	31-62-11	D40738J	26			TB0101Y	B011	1A		YL951
2010B	24	Y2	AJ		3-8	31-62-11	D40738J	26			TB0101Y	B011	1A		YL952-YL954, YN232-YN235
2010B	24	Y2	AJ		5-0	31-62-11	D40738J	26			TB0101Y	B011	1A		YL955-YL999, YN236-YR328
2010R	24	Y2	AJ		0-0	31-62-11	D40738J	25			TB0101Y	A011	1A		YC051-YD158, YL951-YR328
2010Z			AJ		0-0	31-62-11	D40738J	S/R			GB00101	ST..	1A		YC051-YD158, YL951-YR328
2011B	24	Y2	AK		6-4	31-62-11	D04221J	44			TB0101Y	B011	1A		YC051-YD158, YN231
2011B	24	Y2	AK		6-5	31-62-11	D04221J	44			TB0101Y	B011	1A		YL951
2011B	24	Y2	AK		6-6	31-62-11	D04221J	44			TB0101Y	B011	1A		YL952-YL954, YN232-YN235
2011B	24	Y2	AK		6-0	31-62-11	D04221J	44			TB0101Y	B011	1A		YL955-YL999, YN236-YR328
2011R	24	Y2	AK		0-0	31-62-11	D04221J	43			TB0101Y	A011	1A		YC051-YD158, YL951-YR328
2011Z			AK		0-0	31-62-11	D04221J	S/R			GB00101	ST..	1A		YC051-YD158, YL951-YR328
2012B	24	Y2	AL		10-11	31-62-13	D03999	13			D03993	44			YC051-YD158, YN231
2012B	24	Y2	AL		11-0	31-62-13	D03999	13			D03993	44			YL951
2012B	24	Y2	AL		10-6	31-62-13	D03999	13			D03993	44			YL952-YL999, YN232-YR328
2012R	24	Y2	AL		0-0	31-62-13	D03999	14			D03993	25			YC051-YD158, YL951-YR328
2012Z			AL		0-0	31-62-13	D03999	S/R			D03993	S/R			YC051-YD158, YL951-YR328
2013B	24	Y2	AM		9-0	31-62-13	D00331	21			D03993	55			YC051-YD158, YN231

WIRE LIST

D280A108

91-21-11

Section W0000

Page 32

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001			P1 - CAPTAINS INSTRUMENT PANEL (continued)											
2013B	24	Y2	AM		8-10	31-62-13	D00331	21			D03993	55			YL951
2013B	24	Y2	AM		8-7	31-62-13	D00331	21			D03993	55			YL952-YL999, YN232-YR328
2013R	24	Y2	AM		0-0	31-62-13	D00331	19			D03993	18			YC051-YD158, YL951-YR328
2013Z			AM		0-0	31-62-13	D00331	S/R			D03993	S/R			YC051-YD158, YL951-YR328
2014B	24	Y2	AN		4-4	31-62-13	D00423	23			D03993	53			YC051-YD158, YL951-YR328
2014R	24	Y2	AN		0-0	31-62-13	D00423	24			D03993	34			YC051-YD158, YL951-YR328
2014Z			AN		0-0	31-62-13	D00423	S/R			D03993	S/R			YC051-YD158, YL951-YR328
2015B	24	Y2	AP		8-1	27-52-11	D00686	5			D04221J	42			YC051-YD158, YN231
2015B	24	Y2	AP		8-0	27-52-11	D00686	5			D04221J	42			YL951-YL999, YN232-YR328
2015R	24	Y2	AP		0-0	27-52-11	D00686	6			D04221J	41			YC051-YD158, YL951-YR328
2015Z			AP		0-0	27-52-11	D00686	DED			D04221J	S/R			YC051-YD158, YL951-YR328
2016B	24	Y2	AQ		8-1	27-52-11	D00686	13			D04221J	22			YC051-YD158, YN231
2016B	24	Y2	AQ		8-0	27-52-11	D00686	13			D04221J	22			YL951-YL999, YN232-YR328
2016R	24	Y2	AQ		0-0	27-52-11	D00686	12			D04221J	21			YC051-YD158, YL951-YR328
2016Z			AQ		0-0	27-52-11	D00686	DED			D04221J	S/R			YC051-YD158, YL951-YR328
2017B	24	Y2	AR		7-8	34-58-11	D04207J	22			D00714	20	VP		YC053
2017B	24	Y2	AR		7-8	34-58-11	D04207J	22			D00714	20			YC054-YD158, YN231
2017B	24	Y2	AR		7-4	34-58-11	D04207J	22			D00714	20			YL951-YL954, YN232-YN235
2017B	24	Y2	AR		7-3	34-58-11	D04207J	22			D00714	20			YL955-YL999, YN236-YR328
2017R	24	Y2	AR		0-0	34-58-11	D04207J	21			D00714	19	VP		YC053
2017R	24	Y2	AR		0-0	34-58-11	D04207J	21			D00714	19			YC054-YD158, YL951-YR328
2017Z			AR		0-0	34-58-11	D04207J	S/R			D00714	DED			YC053
2017Z			AR		0-0	34-58-11	D04207J	S/R			D00714	S/R			YC054-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0000

Page 33

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)										
201CO				ZM	0-0	31-62-42	D03979A	= 9T			D10030P	= C1			YL951, YN231
201CO				ZM	0-0	31-62-42	D03979A	= 9T			D10030J	= C1			YL952-YL999, YN232-YR328
201CX			OF	ZM	10-5	31-62-42	D03979A	9T			D10030P	= A1			YL951, YN231
201CX			OF	ZM	4-6	31-62-42	D03979A	9T			D10030J	= A1			YL952-YL999, YN232-YR328
3001B	24		Y3	XA	5-4	31-62-11	D03977B	D03			D40738J	23			YC051-YD158, YN231
3001B	24		Y3	XA	4-11	31-62-11	D03977B	D03			D40738J	23			YL951-YL954, YN232-YN235
3001B	24		Y3	XA	5-2	31-62-11	D03977B	D03			D40738J	23			YL955-YL999, YN236-YR328
3001R	24		Y3	XA	0-0	31-62-11	D03977B	C03			D40738J	22			YC051-YD158, YL951-YR328
3001Y	24		Y3	XA	0-0	31-62-11	D03977B	C04			D40738J	24			YC051-YD158, YL951-YR328
3001Z				XA	0-0	31-62-11	D03977B	PERG	1A		D40738J	S/R			YC051-YD158, YL951-YR328
3002B	24		Y3	XB	10-11	31-62-13	D03999	5			D03993	42			YC051-YD158, YN231
3002B	24		Y3	XB	11-0	31-62-13	D03999	5			D03993	42			YL951
3002B	24		Y3	XB	10-6	31-62-13	D03999	5			D03993	42			YL952-YL999, YN232-YR328
3002R	24		Y3	XB	0-0	31-62-13	D03999	8			D03993	41			YC051-YD158, YL951-YR328
3002Y	24		Y3	XB	0-0	31-62-13	D03999	6			D03993	43			YC051-YD158, YL951-YR328
3002Z				XB	0-0	31-62-13	D03999	S/R			D03993	S/R			YC051-YD158, YL951-YR328
3003B	24		Y3	XC	10-11	31-62-13	D03999	10			D03993	23			YC051-YD158, YN231
3003B	24		Y3	XC	11-0	31-62-13	D03999	10			D03993	23			YL951
3003B	24		Y3	XC	10-6	31-62-13	D03999	10			D03993	23			YL952-YL999, YN232-YR328
3003R	24		Y3	XC	0-0	31-62-13	D03999	11			D03993	22			YC051-YD158, YL951-YR328
3003Y	24		Y3	XC	0-0	31-62-13	D03999	9			D03993	24			YC051-YD158, YL951-YR328
3003Z				XC	0-0	31-62-13	D03999	S/R			D03993	S/R			YC051-YD158, YL951-YR328
3004B	24		Y3	XD	9-0	31-62-13	D00331	12			D03993	47			YC051-YD158, YN231
3004B	24		Y3	XD	8-10	31-62-13	D00331	12			D03993	47			YL951

WIRE LIST

D280A108

91-21-11

Section W0000

Page 34

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From			To			Effectivity		
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W0001	286A0001			P1 - CAPTAINS INSTRUMENT PANEL (continued)										
3004B	24	Y3	XD	8-7	31-62-13	D00331	12		D03993	47		YL952-YL999, YN232-YR328		
3004R	24	Y3	XD	0-0	31-62-13	D00331	11		D03993	46		YC051-YD158, YL951-YR328		
3004Y	24	Y3	XD	0-0	31-62-13	D00331	13		D03993	48		YC051-YD158, YL951-YR328		
3004Z			XD	0-0	31-62-13	D00331	S/R		D03993	S/R		YC051-YD158, YL951-YR328		
3005B	24	Y3	XE	9-0	31-62-13	D00331	16		D03993	28		YC051-YD158, YN231		
3005B	24	Y3	XE	8-10	31-62-13	D00331	16		D03993	28		YL951		
3005B	24	Y3	XE	8-7	31-62-13	D00331	16		D03993	28		YL952-YL999, YN232-YR328		
3005R	24	Y3	XE	0-0	31-62-13	D00331	17		D03993	27		YC051-YD158, YL951-YR328		
3005Y	24	Y3	XE	0-0	31-62-13	D00331	15		D03993	29		YC051-YD158, YL951-YR328		
3005Z			XE	0-0	31-62-13	D00331	S/R		D03993	S/R		YC051-YD158, YL951-YR328		
3006B	24	Y3	XF	9-0	31-62-13	D00331	3		D03993	39		YC051-YD158, YN231		
3006B	24	Y3	XF	8-10	31-62-13	D00331	3		D03993	39		YL951		
3006B	24	Y3	XF	8-7	31-62-13	D00331	3		D03993	39		YL952-YL999, YN232-YR328		
3006R	24	Y3	XF	0-0	31-62-13	D00331	2		D03993	38		YC051-YD158, YL951-YR328		
3006Y	24	Y3	XF	0-0	31-62-13	D00331	4		D03993	40		YC051-YD158, YL951-YR328		
3006Z			XF	0-0	31-62-13	D00331	S/R		D03993	S/R		YC051-YD158, YL951-YR328		
3007B	24	Y3	XG	9-0	31-62-13	D00331	7		D03993	9		YC051-YD158, YN231		
3007B	24	Y3	XG	8-10	31-62-13	D00331	7		D03993	9		YL951		
3007B	24	Y3	XG	8-7	31-62-13	D00331	7		D03993	9		YL952-YL999, YN232-YR328		
3007R	24	Y3	XG	0-0	31-62-13	D00331	6		D03993	8		YC051-YD158, YL951-YR328		
3007Y	24	Y3	XG	0-0	31-62-13	D00331	8		D03993	19		YC051-YD158, YL951-YR328		
3007Z			XG	0-0	31-62-13	D00331	S/R		D03993	S/R		YC051-YD158, YL951-YR328		

WIRE LIST

D280A108

91-21-11

Section W0000

Page 35

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001				P1 - CAPTAINS INSTRUMENT PANEL (continued)										
3008B	24	Y3	XH		4-4	31-62-13	D00423	15			D03993	51			YC051-YD158, YL951-YR328
3008R	24	Y3	XH		0-0	31-62-13	D00423	16			D03993	50			YC051-YD158, YL951-YR328
3008Y	24	Y3	XH		0-0	31-62-13	D00423	18			D03993	52			YC051-YD158, YL951-YR328
3008Z			XH		0-0	31-62-13	D00423	S/R			D03993	S/R			YC051-YD158, YL951-YR328
3009B	24	Y3	XJ		4-4	31-62-13	D00423	20			D03993	32			YC051-YD158, YL951-YR328
3009R	24	Y3	XJ		0-0	31-62-13	D00423	21			D03993	31			YC051-YD158, YL951-YR328
3009Y	24	Y3	XJ		0-0	31-62-13	D00423	19			D03993	33			YC051-YD158, YL951-YR328
3009Z			XJ		0-0	31-62-13	D00423	S/R			D03993	S/R			YC051-YD158, YL951-YR328
3010B	20	X3	XK		8-1	27-52-11	D00686	9			D04221J	48			YC051-YD158, YN231
3010B	20	X3	XK		8-0	27-52-11	D00686	9			D04221J	48			YL951-YL999, YN232-YR328
3010R	20	X3	XK		0-0	27-52-11	D00686	10			D04221J	47			YC051-YD158, YL951-YR328
3010Y	20	X3	XK		0-0	27-52-11	D00686	8			D04221J	49			YC051-YD158, YL951-YR328
3010Z			XK		0-0	27-52-11	D00686	DED			D04221J	S/R			YC051-YD158, YL951-YR328
3011B	24	Y3	XL		4-1	31-62-11	D03977B	J01			D02650	7			YC051-YD158, YL955-YN231, YN236-YR328
3011B	24	Y3	XL		4-5	31-62-11	D03977B	J01			D02650	7			YL951
3011B	24	Y3	XL		4-2	31-62-11	D03977B	J01			D02650	7			YL952-YL954, YN232-YN235
3011R	24	Y3	XL		0-0	31-62-11	D03977B	J02			D02650	6			YC051-YD158, YL951-YR328
3011Y	24	Y3	XL		0-0	31-62-11	D03977B	J03			D02650	8			YC051-YD158, YL951-YR328
3011Z			XL		0-0	31-62-11	D03977B	PERG 1A			D02650	S/R			YC051-YD158, YL951-YR328
3012B	24	Y3	XM		4-1	31-62-11	D03979B	J01			D02650	10			YC051-YD158, YN231
3012B	24	Y3	XM		3-9	31-62-11	D03979B	J01			D02650	10			YL951

WIRE LIST

D280A108

91-21-11

Section W0000

Page 36

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W0001	286A0001			P1 - CAPTAINS INSTRUMENT PANEL (continued)										
3012B	24	Y3	XM	3-10	31-62-11	D03979B	J01			D02650	10		YL952-YL999, YN232-YR328	
3012R	24	Y3	XM	0-0	31-62-11	D03979B	J02			D02650	9		YC051-YD158, YL951-YR328	
3012Y	24	Y3	XM	0-0	31-62-11	D03979B	J03			D02650	11		YC051-YD158, YL951-YR328	
3012Z			XM	0-0	31-62-11	D03979B	PERG	1A		D02650	S/R		YC051-YD158, YL951-YR328	
3013B	24	Y3	XN	4-1	31-62-11	D03979B	H01			D02650	13		YC051-YD158, YN231	
3013B	24	Y3	XN	3-9	31-62-11	D03979B	H01			D02650	13		YL951	
3013B	24	Y3	XN	3-10	31-62-11	D03979B	H01			D02650	13		YL952-YL999, YN232-YR328	
3013R	24	Y3	XN	0-0	31-62-11	D03979B	H02			D02650	12		YC051-YD158, YL951-YR328	
3013Y	24	Y3	XN	0-0	31-62-11	D03979B	H03			D02650	14		YC051-YD158, YL951-YR328	
3013Z			XN	0-0	31-62-11	D03979B	PERG	1A		D02650	S/R		YC051-YD158, YL951-YR328	
3014B	24	Y3	XO	5-4	31-62-11	D03981B	J01			D02650	17		YC051-YD158, YN231	
3014B	24	Y3	XO	4-11	31-62-11	D03981B	J01			D02650	17		YL951	
3014B	24	Y3	XO	5-0	31-62-11	D03981B	J01			D02650	17		YL952-YL999, YN232-YR328	
3014R	24	Y3	XO	0-0	31-62-11	D03981B	J02			D02650	16		YC051-YD158, YL951-YR328	
3014Y	24	Y3	XO	0-0	31-62-11	D03981B	J03			D02650	18		YC051-YD158, YL951-YR328	
3014Z			XO	0-0	31-62-11	D03981B	PERG	1A		D02650	S/R		YC051-YD158, YL951-YR328	
301CO			ZG	0-0	31-62-12	D03985A	=4T			D10059	=C1		YC051-YD158, YL951-YR328	
301CX		0F	ZG	4-11	31-62-12	D03985A	4T			D10059	=A1		YC051-YD158, YN231	
301CX		0F	ZG	4-5	31-62-12	D03985A	4T			D10059	=A1		YL951	
301CX		0F	ZG	4-6	31-62-12	D03985A	4T			D10059	=A1		YL952-YL954, YN232-YN235	
301CX		0F	ZG	4-7	31-62-12	D03985A	4T			D10059	=A1		YL955-YL999, YN236-YR328	
302CO			ZH	0-0	31-62-12	D03987A	=4T			D10061	=C1		YC051-YD158, YL951-YR328	
302CX		0F	ZH	4-3	31-62-12	D03987A	4T			D10061	=A1		YC051-YD158, YN231	

WIRE LIST

D280A108

91-21-11

Section W0000

Page 37

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0001	286A0001			P1 - CAPTAINS INSTRUMENT PANEL (continued)											
302CX			0F	ZH	3-10	31-62-12	D03987A	4T			D10061	= A1			YL951
302CX			0F	ZH	3-11	31-62-12	D03987A	4T			D10061	= A1			YL952-YL999, YN232-YR328
303CO				ZI	0-0	31-62-12	D03983A	= 4T			D10063	= C1			YC051-YD158, YL951-YR328
303CX			0F	ZI	4-9	31-62-12	D03983A	4T			D10063	= A1			YC051-YD158, YN231
303CX			0F	ZI	4-4	31-62-12	D03983A	4T			D10063	= A1			YL951-YL999, YN232-YR328
304CO				ZJ	0-0	31-62-12	D03981A	= 4T			D10065	= C1			YC051-YD158, YL951-YR328
304CX			0F	ZJ	3-10	31-62-12	D03981A	4T			D10065	= A1			YC051-YD158, YN231
304CX			0F	ZJ	3-5	31-62-12	D03981A	4T			D10065	= A1			YL951-YL999, YN232-YR328
305CO				ZK	0-0	31-62-12	D03979A	= 4T			D10067	= C1			YC051-YD158, YL951-YR328
305CX			0F	ZK	3-3	31-62-12	D03979A	4T			D10067	= A1			YC051-YD158, YN231
305CX			0F	ZK	2-10	31-62-12	D03979A	4T			D10067	= A1			YL951
305CX			0F	ZK	2-9	31-62-12	D03979A	4T			D10067	= A1			YL952-YL999, YN232-YR328
306CO				ZL	0-0	31-62-12	D03977A	= 4T			D10069	= C1			YC051-YD158, YL951-YR328
306CX			0F	ZL	3-9	31-62-12	D03977A	4T			D10069	= A1			YC051-YD158, YN231
306CX			0F	ZL	3-6	31-62-12	D03977A	4T			D10069	= A1			YL951
306CX			0F	ZL	3-4	31-62-12	D03977A	4T			D10069	= A1			YL952-YL999, YN232-YR328
W0003	286A0003			P3 - F/O INSTRUMENT PANEL											
0007	24		PK		8-6	23-51-21	D04251J	23			D40740J	19			YL951
0007	24		PK		8-5	23-51-21	D04251J	23			D40740J	19			YL952-YL999, YN232-YR328
0007	24		PK		9-0	23-51-21	D04251J	23			D40740J	19			YN231
0008	24		PK		8-6	23-51-21	D04251J	24			D40740J	20			YL951
0008	24		PK		8-5	23-51-21	D04251J	24			D40740J	20			YL952-YL999, YN232-YR328
0008	24		PK		9-0	23-51-21	D04251J	24			D40740J	20			YN231
0037	24		PK		4-11	31-31-15	D40580J	8			TB0201Z	A001	1A		YL963-YL999, YN236-YR328
0038	24		PK		4-10	31-31-15	D40580J	9			TB0201Y	A009	1A		YL963-YL999, YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W0000

Page 38

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W0003	286A0003				P3 - F/O INSTRUMENT PANEL (continued)												
0070	22		PA		18-3	21-33-11		D00895				D40824J				YC060-YC064	
0070	22		PA		9-6	21-33-11		D40824J				D00895				YL951	
0070	22		PA		9-2	21-33-11		D40824J				D00895				YL952-YL999, YN232-YR328	
0070	22		PA		9-4	21-33-11		D40824J				D00895				YN231	
0072	22		PA		18-3	31-53-11		D00895				D40824J				YC060-YC064	
0072	22		PA		9-6	31-53-11		D40824J				D00895				YL951	
0072	22		PA		9-2	31-53-11		D40824J				D00895				YL952-YL999, YN232-YR328	
0072	22		PA		9-4	31-53-11		D40824J				D00895				YN231	
0304	20		CQ		3-2	31-22-11		D00716				GD3010B	DC..	1A		YC054-YD158, YN231	
0304	20		CQ		3-0	31-22-11		D00716				GD3010B	DC..	1A		YL951	
0304	20		CQ		2-11	31-22-11		D00716				GD3010B	DC..	1A		YL952-YL954, YN232-YN235	
0304	20		CQ		2-7	31-22-11		D00716				GD3010B	DC..	1A		YL955-YL999, YN236-YR328	
0327	20		G5		3-5	33-11-21		TB3092W	A001	1		D40740J				YL951-YL954, YN232-YN235	
0327	20		G5		4-9	33-11-21		TB3092W	A001	1		D40740J				YL955-YL999, YN236-YR328	
0327	20		G5		4-4	33-11-21		TB3092W	A001	1		D40740J				YN231	
0328	20		G5		3-8	33-11-21		D40740J				GD3010A	AC..	1		YL951-YL954, YN232-YN235	
0328	20		G5		5-0	33-11-21		D40740J				GD3010A	AC..	1		YL955-YL999, YN236-YR328	
0328	20		G5		4-3	33-11-21		D40740J				GD3010A	AC..	1		YN231	
0501	14		PA		1-11	31-62-21		D03985B				GD03985	DC..	E		YC051-YD158, YN231	
0501	14		PA		2-1	31-62-21		D03985B				GD03985	DC..	E		YL951	
0501	14		PA		2-3	31-62-21		D03985B				GD03985	DC..	E		YL952-YL954, YN232-YN235	
0501	14		PA		2-6	31-62-21		D03985B				GD03985	DC..	E		YL955-YL999, YN236-YR328	
0502	16		PA		2-7	31-62-21		D03985B				GD0301A	ST..	1		YC051-YD158, YN231	
0502	16		PA		2-5	31-62-21		D03985B				GD0301A	ST..	1		YL951	
0502	16		PA		2-3	31-62-21		D03985B				GD0301A	ST..	1		YL952-YL954, YN232-YN235	
0502	16		PA		2-10	31-62-21		D03985B				GD0301A	ST..	1		YL955-YL999, YN236-YR328	
0503	16		PA		2-7	31-62-21		D03985B				GD0301A	ST..	1		YC051-YD158, YN231	

WIRE LIST

D280A108

91-21-11

Section W0000

Page 39

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0003	286A0003				P3 - F/O INSTRUMENT PANEL (continued)										
0503	16		PA		2-5	31-62-21	D03985B		54		GD0301A	ST..	1		YL951
0503	16		PA		2-3	31-62-21	D03985B		54		GD0301A	ST..	1		YL952-YL954, YN232-YN235
0503	16		PA		2-10	31-62-21	D03985B		54		GD0301A	ST..	1		YL955-YL999, YN236-YR328
0504	16		PA		2-7	31-62-21	D03985B		55		GD0301A	ST..	1		YC051-YD158, YN231
0504	16		PA		2-5	31-62-21	D03985B		55		GD0301A	ST..	1		YL951
0504	16		PA		2-3	31-62-21	D03985B		55		GD0301A	ST..	1		YL952-YL954, YN232-YN235
0504	16		PA		2-10	31-62-21	D03985B		55		GD0301A	ST..	1		YL955-YL999, YN236-YR328
0505	16		PA		2-7	31-62-21	D03985B		57		GD0301A	ST..	1		YC051-YD158, YN231
0505	16		PA		2-5	31-62-21	D03985B		57		GD0301A	ST..	1		YL951
0505	16		PA		2-3	31-62-21	D03985B		57		GD0301A	ST..	1		YL952-YL954, YN232-YN235
0505	16		PA		2-10	31-62-21	D03985B		57		GD0301A	ST..	1		YL955-YL999, YN236-YR328
0506	14		PA		1-11	31-62-21	D03987B		58		GD03987	DC..	E		YC051-YD158, YN231
0506	14		PA		2-4	31-62-21	D03987B		58		GD03987	DC..	E		YL951
0506	14		PA		2-0	31-62-21	D03987B		58		GD03987	DC..	E		YL952-YL999, YN232-YR328
0507	16		PA		2-11	31-62-21	D03987B		53		GD0301A	ST..	1		YC051-YD158, YN231
0507	16		PA		3-3	31-62-21	D03987B		53		GD0301A	ST..	1		YL951
0507	16		PA		3-1	31-62-21	D03987B		53		GD0301A	ST..	1		YL952-YL954, YN232-YN235
0507	16		PA		3-5	31-62-21	D03987B		53		GD0301A	ST..	1		YL955-YL999, YN236-YR328
0508	16		PA		2-11	31-62-21	D03987B		54		GD0301A	ST..	1		YC051-YD158, YN231
0508	16		PA		3-3	31-62-21	D03987B		54		GD0301A	ST..	1		YL951
0508	16		PA		3-1	31-62-21	D03987B		54		GD0301A	ST..	1		YL952-YL954, YN232-YN235
0508	16		PA		3-5	31-62-21	D03987B		54		GD0301A	ST..	1		YL955-YL999, YN236-YR328
0509	16		PA		2-11	31-62-21	D03987B		55		GD0301A	ST..	1		YC051-YD158, YN231
0509	16		PA		3-3	31-62-21	D03987B		55		GD0301A	ST..	1		YL951
0509	16		PA		3-1	31-62-21	D03987B		55		GD0301A	ST..	1		YL952-YL954, YN232-YN235
0509	16		PA		3-5	31-62-21	D03987B		55		GD0301A	ST..	1		YL955-YL999, YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W0000

Page 40

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W0003	286A0003				P3 - F/O INSTRUMENT PANEL (continued)											
0510	16		PA		2-11	31-62-21		D03987B	57			GD0301A	ST..	1		YC051-YD158, YN231
0510	16		PA		3-3	31-62-21		D03987B	57			GD0301A	ST..	1		YL951
0510	16		PA		3-1	31-62-21		D03987B	57			GD0301A	ST..	1		YL952-YL954, YN232-YN235
0510	16		PA		3-5	31-62-21		D03987B	57			GD0301A	ST..	1		YL955-YL999, YN236-YR328
0511	14		PA		2-3	31-62-21		D03983B	58			GD03983	DC..	E		YC051-YD158, YL951-YR328
0512	16		PA		2-2	31-62-21		D03983B	53			GD0901A	ST..	1		YC051-YD158, YN231
0512	16		PA		2-3	31-62-21		D03983B	53			GD0901A	ST..	1		YL951-YL999, YN232-YR328
0513	16		PA		2-2	31-62-21		D03983B	54			GD0901A	ST..	1		YC051-YD158, YN231
0513	16		PA		2-3	31-62-21		D03983B	54			GD0901A	ST..	1		YL951-YL999, YN232-YR328
0514	16		PA		2-2	31-62-21		D03983B	55			GD0901A	ST..	1		YC051-YD158, YN231
0514	16		PA		2-3	31-62-21		D03983B	55			GD0901A	ST..	1		YL951-YL999, YN232-YR328
0515	16		PA		2-2	31-62-21		D03983B	57			GD0901A	ST..	1		YC051-YD158, YN231
0515	16		PA		2-3	31-62-21		D03983B	57			GD0901A	ST..	1		YL951-YL999, YN232-YR328
0516	20		PA		5-5	31-62-21		D40740J	27			GD0301B	ST..	1A		YC051-YD158, YN231
0516	20		PA		3-9	31-62-21		D40740J	27			GD0301B	ST..	1A		YL951-YL954, YN232-YN235
0516	20		PA		5-4	31-62-21		D40740J	27			GD0301B	ST..	1A		YL955-YL999, YN236-YR328
0532	22		PA		2-2	31-62-22		D03983B	B01			GD0901C	DC..	1A		YC051-YD158, YN231
0532	22		PA		2-3	31-62-22		D03983B	B01			GD0901C	DC..	1A		YL951-YL999, YN232-YR328
0533	22		PA		2-2	31-62-22		D03983B	C01			GD0901C	DC..	1A		YC051-YD158, YN231
0533	22		PA		2-3	31-62-22		D03983B	C01			GD0901C	DC..	1A		YL951-YL999, YN232-YR328
0534	22		PA		2-8	31-62-22		D03985B	A01			GD0301C	DC..	1A		YC051-YD158, YN231
0534	22		PA		2-6	31-62-22		D03985B	A01			GD0301C	DC..	1A		YL951
0534	22		PA		2-4	31-62-22		D03985B	A01			GD0301C	DC..	1A		YL952-YL954, YN232-YN235
0534	22		PA		3-0	31-62-22		D03985B	A01			GD0301C	DC..	1A		YL955-YL999, YN236-YR328
0535	22		PA		2-8	31-62-22		D03985B	C01			GD0301C	DC..	1A		YC051-YD158, YN231
0535	22		PA		2-6	31-62-22		D03985B	C01			GD0301C	DC..	1A		YL951

WIRE LIST

D280A108

91-21-11

Section W0000

Page 41

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0003	286A0003				P3 - F/O INSTRUMENT PANEL (continued)										
0535	22		PA		2-4	31-62-22	D03985B		C01		GD0301C	DC..	1A		YL952-YL954, YN232-YN235
0535	22		PA		3-0	31-62-22	D03985B		C01		GD0301C	DC..	1A		YL955-YL999, YN236-YR328
0536	22		G5		3-0	31-62-22	D03987B		C01		GD0301D	DC..	1A		YC051-YD158, YN231
0536	22		G5		3-5	31-62-22	D03987B		C01		GD0301D	DC..	1A		YL951
0536	22		G5		3-3	31-62-22	D03987B		C01		GD0301D	DC..	1A		YL952-YL954, YN232-YN235
0536	22		G5		3-8	31-62-22	D03987B		C01		GD0301D	DC..	1A		YL955-YL999, YN236-YR328
0537	22		G5		3-0	31-62-22	D03987B		E01		GD0301D	DC..	1A		YC051-YD158, YN231
0537	22		G5		3-5	31-62-22	D03987B		E01		GD0301D	DC..	1A		YL951
0537	22		G5		3-3	31-62-22	D03987B		E01		GD0301D	DC..	1A		YL952-YL954, YN232-YN235
0537	22		G5		3-8	31-62-22	D03987B		E01		GD0301D	DC..	1A		YL955-YL999, YN236-YR328
0546	22		PA		3-10	31-62-23	D03991		17		GD0301C	DC..	1A		YC051-YD158, YN231
0546	22		PA		5-2	31-62-23	D03991		17		GD0301C	DC..	1A		YL951-YL954, YN232-YN235
0546	22		PA		6-1	31-62-23	D03991		17		GD0301C	DC..	1A		YL955-YL999, YN236-YR328
0547	22		PA		3-10	31-62-23	D03991		22		GD0301C	DC..	1A		YC051-YD158, YN231
0547	22		PA		5-2	31-62-23	D03991		22		GD0301C	DC..	1A		YL951-YL954, YN232-YN235
0547	22		PA		6-1	31-62-23	D03991		22		GD0301C	DC..	1A		YL955-YL999, YN236-YR328
0548	22		PA		6-6	31-62-23	D00333		4		GD0201D	DC..	1A		YC051-YD158, YN231
0548	22		PA		6-5	31-62-23	D00333		4		GD0201D	DC..	1A		YL951
0548	22		PA		6-4	31-62-23	D00333		4		GD0201D	DC..	1A		YL952-YL999, YN232-YR328
0549	22		PA		6-6	31-62-23	D00333		8		GD0201D	DC..	1A		YC051-YD158, YN231
0549	22		PA		6-5	31-62-23	D00333		8		GD0201D	DC..	1A		YL951
0549	22		PA		6-4	31-62-23	D00333		8		GD0201D	DC..	1A		YL952-YL999, YN232-YR328
0550	22		PA		6-6	31-62-23	D00333		13		GD0201D	DC..	1A		YC051-YD158, YN231
0550	22		PA		6-5	31-62-23	D00333		13		GD0201D	DC..	1A		YL951
0550	22		PA		6-4	31-62-23	D00333		13		GD0201D	DC..	1A		YL952-YL999, YN232-YR328
0551	22		PA		6-6	31-62-23	D00333		17		GD0201D	DC..	1A		YC051-YD158, YN231

WIRE LIST

D280A108

91-21-11

Section W0000

Page 42

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0003	286A0003			P3 - F/O INSTRUMENT PANEL (continued)											
0551	22		PA		6-5	31-62-23	D00333	17			GD0201D	DC..	1A		YL951
0551	22		PA		6-4	31-62-23	D00333	17			GD0201D	DC..	1A		YL952-YL999, YN232-YR328
0552	22		PA		6-6	31-62-23	D00333	23			GD0201D	DC..	1A		YC051-YD158, YN231
0552	22		PA		6-5	31-62-23	D00333	23			GD0201D	DC..	1A		YL951
0552	22		PA		6-4	31-62-23	D00333	23			GD0201D	DC..	1A		YL952-YL999, YN232-YR328
0554	22		PA		4-5	31-62-23	D00895	17			GD0101D	DC..	1A		YC051-YD158, YN231
0554	22		PA		5-1	31-62-23	D00895	17			GD0101D	DC..	1A		YL951
0554	22		PA		5-2	31-62-23	D00895	17			GD0101D	DC..	1A		YL952-YL954, YN232-YN235
0554	22		PA		5-5	31-62-23	D00895	17			GD0101D	DC..	1A		YL955-YL999, YN236-YR328
0555	22		PA		4-5	31-62-23	D00895	22			GD0101D	DC..	1A		YC051-YD158, YN231
0555	22		PA		5-1	31-62-23	D00895	22			GD0101D	DC..	1A		YL951
0555	22		PA		5-2	31-62-23	D00895	22			GD0101D	DC..	1A		YL952-YL954, YN232-YN235
0555	22		PA		5-5	31-62-23	D00895	22			GD0101D	DC..	1A		YL955-YL999, YN236-YR328
0578	20		CQ		3-11	22-14-11	D02439	3			GD0301B	DC..	1A		YC051-YD158, YN231
0578	20		CQ		4-8	22-14-11	D02439	3			GD0301B	DC..	1A		YL951
0578	20		CQ		4-9	22-14-11	D02439	3			GD0301B	DC..	1A		YL952-YL954, YN232-YN235
0578	20		CQ		5-1	22-14-11	D02439	3			GD0301B	DC..	1A		YL955-YL999, YN236-YR328
0579	22		G5		5-1	22-14-11	D02439	5			TB0301Y	A015	1A		YC051-YD158, YN231
0579	22		G5		5-2	22-14-11	D02439	5			TB0301Y	A015	1A		YL951
0579	22		G5		5-3	22-14-11	D02439	5			TB0301Y	A015	1A		YL952-YL954, YN232-YN235
0579	22		G5		4-9	22-14-11	D02439	5			TB0301Y	A015	1A		YL955-YL999, YN236-YR328
0580	22		G5		5-1	22-14-11	D02439	6			TB0301Y	A015	1A		YC051-YD158, YN231
0580	22		G5		5-2	22-14-11	D02439	6			TB0301Y	A015	1A		YL951
0580	22		G5		5-3	22-14-11	D02439	6			TB0301Y	A015	1A		YL952-YL954, YN232-YN235
0580	22		G5		4-9	22-14-11	D02439	6			TB0301Y	A015	1A		YL955-YL999, YN236-YR328
0581	22		G5		5-1	22-14-11	D02439	8			TB0301Y	B015	1A		YC051-YD158, YN231
0581	22		G5		5-2	22-14-11	D02439	8			TB0301Y	B015	1A		YL951

WIRE LIST

D280A108

91-21-11

Section W0000

Page 43

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W0003	286A0003				P3 - F/O INSTRUMENT PANEL (continued)												
0581	22		G5		5-3	22-14-11	D02439			8		TB0301Y	B015	1A		YL952-YL954, YN232-YN235	
0581	22		G5		4-9	22-14-11	D02439			8		TB0301Y	B015	1A		YL955-YL999, YN236-YR328	
0582	22		G5		5-1	22-14-11	D02439			7		TB0301Y	B015	1A		YC051-YD158, YN231	
0582	22		G5		5-2	22-14-11	D02439			7		TB0301Y	B015	1A		YL951	
0582	22		G5		5-3	22-14-11	D02439			7		TB0301Y	B015	1A		YL952-YL954, YN232-YN235	
0582	22		G5		4-9	22-14-11	D02439			7		TB0301Y	B015	1A		YL955-YL999, YN236-YR328	
0583	22		CQ		5-0	22-14-11	D02439			12		TB0301Y	A019	1A		YC051-YD158, YN231	
0583	22		CQ		5-2	22-14-11	D02439			12		TB0301Y	A019	1A		YL951	
0583	22		CQ		5-4	22-14-11	D02439			12		TB0301Y	A019	1A		YL952-YL954, YN232-YN235	
0583	22		CQ		4-10	22-14-11	D02439			12		TB0301Y	A019	1A		YL955-YL999, YN236-YR328	
0584	22		G5		8-5	22-14-11	D02439			9		D04251J		5		YC051-YD158, YN231	
0584	22		G5		8-6	22-14-11	D02439			9		D04251J		5		YL951	
0584	22		G5		8-2	22-14-11	D02439			9		D04251J		5		YL952-YL999, YN232-YR328	
0585	22		CQ		5-0	22-14-11	D02439			13		TB0301Z	A021	1A		YC051-YD158, YN231	
0585	22		CQ		5-3	22-14-11	D02439			13		TB0301Z	A021	1A		YL951	
0585	22		CQ		5-5	22-14-11	D02439			13		TB0301Z	A021	1A		YL952-YL954, YN232-YN235	
0585	22		CQ		4-10	22-14-11	D02439			13		TB0301Z	A021	1A		YL955-YL999, YN236-YR328	
0586	22		CQ		5-0	22-14-11	D02439			14		TB0301Z	A021	1A		YC051-YD158, YN231	
0586	22		CQ		5-3	22-14-11	D02439			14		TB0301Z	A021	1A		YL951	
0586	22		CQ		5-5	22-14-11	D02439			14		TB0301Z	A021	1A		YL952-YL954, YN232-YN235	
0586	22		CQ		4-10	22-14-11	D02439			14		TB0301Z	A021	1A		YL955-YL999, YN236-YR328	
0587	22		CQ		5-0	22-14-11	D02439			4		TB0301Z	A021	1A		YC051-YD158, YN231	
0587	22		CQ		5-3	22-14-11	D02439			4		TB0301Z	A021	1A		YL951	
0587	22		CQ		5-5	22-14-11	D02439			4		TB0301Z	A021	1A		YL952-YL954, YN232-YN235	
0587	22		CQ		4-10	22-14-11	D02439			4		TB0301Z	A021	1A		YL955-YL999, YN236-YR328	

WIRE LIST

D280A108

91-21-11

Section W0000

Page 44

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W0003	286A0003				P3 - F/O INSTRUMENT PANEL (continued)												
0588	22		CQ		4-11	22-14-11	D02441			6		TB0301Z	A021	1A	YC051-YD158, YL955-YN231, YN236-YR328		
0588	22		CQ		5-4	22-14-11	D02441			6		TB0301Z	A021	1A	YL951		
0588	22		CQ		5-5	22-14-11	D02441			6		TB0301Z	A021	1A	YL952-YL954, YN232-YN235		
0589	22		CQ		4-11	22-14-11	D02441			7		TB0301Z	A021	1A	YC051-YD158, YL955-YN231, YN236-YR328		
0589	22		CQ		5-4	22-14-11	D02441			7		TB0301Z	A021	1A	YL951		
0589	22		CQ		5-5	22-14-11	D02441			7		TB0301Z	A021	1A	YL952-YL954, YN232-YN235		
0590	22		CQ		8-10	22-14-11	D02435			12		TB0301Y	A019	1A	YC051-YD158, YL952-YL954, YN231-YN235		
0590	22		CQ		8-11	22-14-11	D02435			12		TB0301Y	A019	1A	YL951		
0590	22		CQ		8-4	22-14-11	D02435			12		TB0301Y	A019	1A	YL955-YL999, YN236-YR328		
0591	22		G5		6-5	22-14-11	D04251J			2		TB0301Y	A015	1A	YC051-YD158, YN231		
0591	22		G5		6-6	22-14-11	D04251J			2		TB0301Y	A015	1A	YL951		
0591	22		G5		6-7	22-14-11	D04251J			2		TB0301Y	A015	1A	YL952-YL954, YN232-YN235		
0591	22		G5		6-1	22-14-11	D04251J			2		TB0301Y	A015	1A	YL955-YL999, YN236-YR328		
0592	22		G5		6-5	22-14-11	D04251J			4		TB0301Y	B015	1A	YC051-YD158, YN231		
0592	22		G5		6-6	22-14-11	D04251J			4		TB0301Y	B015	1A	YL951		
0592	22		G5		6-7	22-14-11	D04251J			4		TB0301Y	B015	1A	YL952-YL954, YN232-YN235		
0592	22		G5		6-1	22-14-11	D04251J			4		TB0301Y	B015	1A	YL955-YL999, YN236-YR328		
0593	22		CQ		6-5	22-14-11	D04251J			11		TB0301Y	A019	1A	YC051-YD158, YN231		
0593	22		CQ		6-7	22-14-11	D04251J			11		TB0301Y	A019	1A	YL951		
0593	22		CQ		6-8	22-14-11	D04251J			11		TB0301Y	A019	1A	YL952-YL954, YN232-YN235		
0593	22		CQ		6-2	22-14-11	D04251J			11		TB0301Y	A019	1A	YL955-YL999, YN236-YR328		
0594	22		CQ		6-5	22-14-11	D04251J			6		TB0301Z	A021	1A	YC051-YD158, YN231		
0594	22		CQ		6-8	22-14-11	D04251J			6		TB0301Z	A021	1A	YL951		

WIRE LIST

D280A108

91-21-11

Section W0000

Page 45

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W0003	286A0003				P3 - F/O INSTRUMENT PANEL (continued)												
0594	22		CQ		6-9	22-14-11	D04251J		6		TB0301Z	A021	1A		YL952-YL954, YN232-YN235		
0594	22		CQ		6-3	22-14-11	D04251J		6		TB0301Z	A021	1A		YL955-YL999, YN236-YR328		
0595	22		CQ		8-11	27-54-11	D03991		6		D04221J	13			YC051-YD158, YN231		
0595	22		CQ		9-6	27-54-11	D03991		6		D04221J	13			YL951		
0595	22		CQ		9-2	27-54-11	D03991		6		D04221J	13			YL952-YL999, YN232-YR328		
0596	24		PK		2-10	32-44-11	D40824J		38		D40580J	7			YC051-YD158, YL951-YR328		
0600	22		G5		8-5	22-31-11	D02439		15		D04251J	7			YC051-YD155		
0600	22		G5		8-7	22-14-11	D02439		15		TB0101Y	A003	1A		YD157-YD158, YN231		
0600	22		G5		8-11	22-14-11	D02439		15		TB0101Y	A003	1A		YL951		
0600	22		G5		8-9	22-14-11	D02439		15		TB0101Y	A003	1A		YL952-YL954, YN232-YN235		
0600	22		G5		8-3	22-14-11	D02439		15		TB0101Y	A003	1A		YL955-YL999, YN236-YR328		
0601	22		PA		8-5	22-31-51	D02439		10		D04251J	8			YC051-YD158, YN231		
0601	22		PA		8-6	22-31-51	D02439		10		D04251J	8			YL951		
0601	22		PA		8-2	22-31-51	D02439		10		D04251J	8			YL952-YL999, YN232-YR328		
0602	22		PA		6-11	34-61-16	D04251J		10		TB0101Y	B003	1A		YC051-YD158, YL955-YN231, YN236-YR328		
0602	22		PA		7-4	34-61-16	D04251J		10		TB0101Y	B003	1A		YL951		
0602	22		PA		7-5	34-61-16	D04251J		10		TB0101Y	B003	1A		YL952-YL954, YN232-YN235		
0603	22		PA		4-11	34-61-16	D02437		8		TB0101Y	B003	1A		YC051-YD158, YL955-YN231, YN236-YR328		
0603	22		PA		5-3	34-61-16	D02437		8		TB0101Y	B003	1A		YL951		
0603	22		PA		5-5	34-61-16	D02437		8		TB0101Y	B003	1A		YL952-YL954, YN232-YN235		
0604	22		PA		3-10	34-61-16	D02441		3		GD0301B	DC..	1A		YC051-YD158, YN231		
0604	22		PA		4-9	34-61-16	D02441		3		GD0301B	DC..	1A		YL951		
0604	22		PA		4-10	34-61-16	D02441		3		GD0301B	DC..	1A		YL952-YL954, YN232-YN235		
0604	22		PA		5-2	34-61-16	D02441		3		GD0301B	DC..	1A		YL955-YL999, YN236-YR328		

WIRE LIST

D280A108

91-21-11

Section W0000

Page 46

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W0003	286A0003				P3 - F/O INSTRUMENT PANEL (continued)												
0605	22		PA		8-6		34-61-16	D02441			8		TB0101Y	B003	1A		YC051-YD158, YN231
0605	22		PA		9-0		34-61-16	D02441			8		TB0101Y	B003	1A		YL951
0605	22		PA		8-10		34-61-16	D02441			8		TB0101Y	B003	1A		YL952-YL954, YN232-YN235
0605	22		PA		8-4		34-61-16	D02441			8		TB0101Y	B003	1A		YL955-YL999, YN236-YR328
0609	22		PA		6-7		34-41-11	D01205		CAP	Y		D04237J	33			YC051-YC052
0609	22		PA		6-7		SPARE	D01205		CAP	Y		D04237J	33			YC053-YD158, YN231
0609	22		PA		6-5		SPARE	D01205		CAP	Y		D04237J	33			YL951
0609	22		PA		6-6		SPARE	D01205		CAP	Y		D04237J	33			YL952-YL999, YN232-YR328
0610	22		CQ		7-9		29-32-11	D40924J			23		D02678	3			YC051-YD158, YL952-YR328
0610	22		CQ		8-1		29-32-11	D40924J			23		D02678	3			YL951
0624	24		PK		6-10		32-64-12	D11732			13		D40580J	4			YC051-YD158, YN231
0624	24		PK		7-0		32-64-12	D11732			13		D40580J	4			YL951-YL999, YN232-YR328
0625	24		PK		6-10		32-64-12	D11732			25		D40580J	5			YC051-YD158, YN231
0625	24		PK		7-0		32-64-12	D11732			25		D40580J	5			YL951-YL999, YN232-YR328
0626	24		PK		6-10		32-64-12	D11732			4		D40580J	6			YC051-YD158, YN231
0626	24		PK		7-0		32-64-12	D11732			4		D40580J	6			YL951-YL999, YN232-YR328
0627	24		PK		8-6		34-49-11	D03991			12		TB0101Y	A009	1A		YC051-YD158, YL955-YN231, YN236-YR328
0627	24		PK		9-2		34-49-11	D03991			12		TB0101Y	A009	1A		YL951
0627	24		PK		9-0		34-49-11	D03991			12		TB0101Y	A009	1A		YL952-YL954, YN232-YN235
0628	22		PA		3-10		34-49-11	D03991			13		GD0301B	DC..	1A		YC051-YD158, YN231
0628	22		PA		5-1		34-49-11	D03991			13		GD0301B	DC..	1A		YL951-YL954, YN232-YN235
0628	22		PA		6-0		34-49-11	D03991			13		GD0301B	DC..	1A		YL955-YL999, YN236-YR328
0629	24		PK		8-6		34-49-11	D03991			11		TB0101Y	B009	1A		YC051-YD158, YL955-YN231, YN236-YR328
0629	24		PK		9-2		34-49-11	D03991			11		TB0101Y	B009	1A		YL951

WIRE LIST

D280A108

91-21-11

Section W0000

Page 47

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0003	286A0003				P3 - F/O INSTRUMENT PANEL (continued)										
0629	24		PK		9-0	34-49-11	D03991		11		TB0101Y	B009	1A		YL952-YL954, YN232-YN235
0630	24		G6		7-5	34-49-11	D01205		5		D04221J	25			YC051-YD158, YN231
0630	24		G6		7-3	34-49-11	D01205		5		D04221J	25			YL951
0630	24		G6		7-4	34-49-11	D01205		5		D04221J	25			YL952-YL999, YN232-YR328
0631	22		PA		4-3	34-49-11	D01205		6		GD0301B	DC..	1A		YC051-YD158, YL955-YN231, YN236-YR328
0631	22		PA		4-1	34-49-11	D01205		6		GD0301B	DC..	1A		YL951
0631	22		PA		3-11	34-49-11	D01205		6		GD0301B	DC..	1A		YL952-YL954, YN232-YN235
0632	24		G6		7-5	34-49-11	D01205		7		D04221J	27			YC051-YD158, YN231
0632	24		G6		7-3	34-49-11	D01205		7		D04221J	27			YL951
0632	24		G6		7-4	34-49-11	D01205		7		D04221J	27			YL952-YL999, YN232-YR328
0633	24		G6		7-5	34-49-11	D01205		4		D04221J	28			YC051-YD158, YN231
0633	24		G6		7-3	34-49-11	D01205		4		D04221J	28			YL951
0633	24		G6		7-4	34-49-11	D01205		4		D04221J	28			YL952-YL999, YN232-YR328
0634	22		PA		4-3	34-49-11	D01205		3		GD0301B	DC..	1A		YC051-YD158, YL955-YN231, YN236-YR328
0634	22		PA		4-1	34-49-11	D01205		3		GD0301B	DC..	1A		YL951
0634	22		PA		3-11	34-49-11	D01205		3		GD0301B	DC..	1A		YL952-YL954, YN232-YN235
0635	24		G6		7-5	34-49-11	D01205		8		D04221J	29			YC051-YD158, YN231
0635	24		G6		7-3	34-49-11	D01205		8		D04221J	29			YL951
0635	24		G6		7-4	34-49-11	D01205		8		D04221J	29			YL952-YL999, YN232-YR328
0636	22		G5		6-3	34-49-11	D01205		9		TB0201Z	A001	1A		YC051-YD158, YN231
0636	22		G5		5-4	34-49-11	D01205		9		TB0201Z	A001	1A		YL951
0636	22		G5		5-5	34-49-11	D01205		9		TB0201Z	A001	1A		YL952-YL999, YN232-YR328
0637	24		B6		5-3	31-22-11	D40924J		27		TB3092Y	A009	1A		YC051-YD158, YN231
0637	24		B6		5-5	31-22-11	D40924J		27		TB3092Y	A009	1A		YL951
0637	24		B6		6-3	31-22-11	D40924J		27		TB3092Y	A009	1A		YL952-YL954, YN232-YN235

WIRE LIST

D280A108

91-21-11

Section W0000

Page 48

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0003	286A0003			P3 - F/O INSTRUMENT PANEL (continued)											
0637	24		B6		5-0	31-22-11	D40924J	27			TB3092Y	A009	1A		YL955-YL999, YN236-YR328
0638	24		B6		5-3	31-22-11	D40924J	28			TB3092Y	B009	1A		YC051-YD158, YN231
0638	24		B6		5-5	31-22-11	D40924J	28			TB3092Y	B009	1A		YL951
0638	24		B6		6-3	31-22-11	D40924J	28			TB3092Y	B009	1A		YL952-YL954, YN232-YN235
0638	24		B6		5-0	31-22-11	D40924J	28			TB3092Y	B009	1A		YL955-YL999, YN236-YR328
0639	24		B6		3-2	31-22-11	D00716	3			TB3092Y	A009	1A		YC051-YD158, YN231
0639	24		B6		2-9	31-22-11	D00716	3			TB3092Y	A009	1A		YL951
0639	24		B6		2-8	31-22-11	D00716	3			TB3092Y	A009	1A		YL952-YL954, YN232-YN235
0639	24		B6		3-0	31-22-11	D00716	3			TB3092Y	A009	1A		YL955-YL999, YN236-YR328
0640	24		B6		3-2	31-22-11	D00716	8			TB3092Y	B009	1A		YC051-YD158, YN231
0640	24		B6		2-9	31-22-11	D00716	8			TB3092Y	B009	1A		YL951
0640	24		B6		2-8	31-22-11	D00716	8			TB3092Y	B009	1A		YL952-YL954, YN232-YN235
0640	24		B6		3-0	31-22-11	D00716	8			TB3092Y	B009	1A		YL955-YL999, YN236-YR328
0641	24		B6		0-7	31-22-11	D00716	13			D00716	14			YC051-YD158, YL951-YR328
0642	20		CQ		4-5	31-22-11	D00716	7			GD0301B	ST..	1A		YC051-YD158, YN231
0642	20		CQ		3-0	31-22-11	D00716	7			GD0301B	ST..	1A		YL951-YL954, YN232-YN235
0642	20		CQ		2-3	31-22-11	D00716	7			GD0301B	ST..	1A		YL955-YL999, YN236-YR328
0643	20		CQ		4-5	31-22-11	D00716	9			GD0301B	DC..	1A		YC051-YD158, YN231
0643	20		CQ		3-0	31-22-11	D00716	9			GD0301B	DC..	1A		YL951-YL954, YN232-YN235
0643	20		CQ		2-3	31-22-11	D00716	9			GD0301B	DC..	1A		YL955-YL999, YN236-YR328
0644	20		CQ		6-2	31-52-11	D40824J	14			TB3092Z	B021	1A		YC051-YD158, YL955-YN231, YN236-YR328
0644	20		CQ		6-8	31-52-11	D40824J	14			TB3092Z	B021	1A		YL951-YL954, YN232-YN235
0645	20		CQ		6-2	31-52-11	D40824J	11			TB3092Y	B019	1A		YC051-YD158, YN231

WIRE LIST

D280A108

91-21-11

Section W0000

Page 49

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W0003	286A0003				P3 - F/O INSTRUMENT PANEL (continued)												
0645	20		CQ		6-7	31-52-11	D40824J		11		TB3092Y	B019	1A		YL951-YL954, YN232-YN235		
0645	20		CQ		6-1	31-52-11	D40824J		11		TB3092Y	B019	1A		YL955-YL999, YN236-YR328		
0646	20		CQ		6-2	31-52-11	D40824J		13		TB3092Y	A019	1A		YC051-YD158, YN231		
0646	20		CQ		6-7	31-52-11	D40824J		13		TB3092Y	A019	1A		YL951-YL954, YN232-YN235		
0646	20		CQ		6-1	31-52-11	D40824J		13		TB3092Y	A019	1A		YL955-YL999, YN236-YR328		
0648	20		CQ		8-10	31-52-11	D40740J		4		D40824J		12		YC051-YD158, YN231		
0648	20		CQ		8-5	31-52-11	D40740J		4		D40824J		12		YL951		
0648	20		CQ		8-4	31-52-11	D40740J		4		D40824J		12		YL952-YL999, YN232-YR328		
0649	20		CQ		4-1	31-52-11	D40740J		6		TB3092Y	B019	1A		YC051-YD158, YN231		
0649	20		CQ		3-8	31-52-11	D40740J		6		TB3092Y	B019	1A		YL951		
0649	20		CQ		3-9	31-52-11	D40740J		6		TB3092Y	B019	1A		YL952-YL954, YN232-YN235		
0649	20		CQ		5-0	31-52-11	D40740J		6		TB3092Y	B019	1A		YL955-YL999, YN236-YR328		
0650	20		CQ		4-2	31-52-11	D40740J		7		TB3092Z	B021	1A		YC051-YD158, YN231		
0650	20		CQ		3-8	31-52-11	D40740J		7		TB3092Z	B021	1A		YL951		
0650	20		CQ		3-10	31-52-11	D40740J		7		TB3092Z	B021	1A		YL952-YL954, YN232-YN235		
0650	20		CQ		5-1	31-52-11	D40740J		7		TB3092Z	B021	1A		YL955-YL999, YN236-YR328		
0651	20		CQ		4-2	31-52-11	D40740J		3		TB3092Z	B021	1A		YC051-YD158, YN231		
0651	20		CQ		3-8	31-52-11	D40740J		3		TB3092Z	B021	1A		YL951		
0651	20		CQ		3-10	31-52-11	D40740J		3		TB3092Z	B021	1A		YL952-YL954, YN232-YN235		
0651	20		CQ		5-1	31-52-11	D40740J		3		TB3092Z	B021	1A		YL955-YL999, YN236-YR328		
0652	20		CQ		4-0	31-52-11	D40740J		2		GD3010C	DC..	1A		YC051-YD158, YN231		
0652	20		CQ		3-9	31-52-11	D40740J		2		GD3010C	DC..	1A		YL951-YL954, YN232-YN235		
0652	20		CQ		5-0	31-52-11	D40740J		2		GD3010C	DC..	1A		YL955-YL999, YN236-YR328		
0653	20		CQ		4-1	31-52-11	D40740J		1		TB3092Y	A019	1A		YC051-YD158, YN231		
0653	20		CQ		3-8	31-52-11	D40740J		1		TB3092Y	A019	1A		YL951		

WIRE LIST

D280A108

91-21-11

Section W0000

Page 50

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W0003	286A0003				P3 - F/O INSTRUMENT PANEL (continued)											
0653	20		CQ		3-9		31-52-11	D40740J		1		TB3092Y	A019	1A		YL952-YL954, YN232-YN235
0653	20		CQ		5-0		31-52-11	D40740J		1		TB3092Y	A019	1A		YL955-YL999, YN236-YR328
0655	20		CQ		8-10		31-52-21	D40740J		9		D40824J	2			YC051-YD158, YN231
0655	20		CQ		8-5		31-52-21	D40740J		9		D40824J	2			YL951
0655	20		CQ		8-4		31-52-21	D40740J		9		D40824J	2			YL952-YL999, YN232-YR328
0656	20		CQ		8-10		31-52-51	D40740J		13		D40824J	4			YC051-YD158, YN231
0656	20		CQ		8-5		31-52-51	D40740J		13		D40824J	4			YL951
0656	20		CQ		8-4		31-52-51	D40740J		13		D40824J	4			YL952-YL999, YN232-YR328
0657	20		CQ		8-10		31-52-55	D40740J		8		D40824J	3			YC051-YD158, YN231
0657	20		CQ		8-5		31-52-55	D40740J		8		D40824J	3			YL951
0657	20		CQ		8-4		31-52-55	D40740J		8		D40824J	3			YL952-YL999, YN232-YR328
0658	20		CQ		8-10		31-52-61	D40740J		11		D40824J	5			YC051-YD158, YN231
0658	20		CQ		8-5		31-52-61	D40740J		11		D40824J	5			YL951
0658	20		CQ		8-4		31-52-61	D40740J		11		D40824J	5			YL952-YL999, YN232-YR328
0659	20		CQ		8-10		31-52-65	D40740J		10		D40824J	8			YC051-YD158, YN231
0659	20		CQ		8-5		31-52-65	D40740J		10		D40824J	8			YL951
0659	20		CQ		8-4		31-52-65	D40740J		10		D40824J	8			YL952-YL999, YN232-YR328
0660	20		CQ		8-10		31-52-75	D40740J		12		D40824J	9			YC051-YD158, YN231
0660	20		CQ		8-5		31-52-75	D40740J		12		D40824J	9			YL951
0660	20		CQ		8-4		31-52-75	D40740J		12		D40824J	9			YL952-YL999, YN232-YR328
0661	16		PA		6-10		33-11-21	D46033J		27		D01038	15			YC051-YD158, YN231
0661	16		PA		6-8		33-11-21	D46033J		27		D01038	15			YL951
0661	16		PA		6-9		33-11-21	D46033J		27		D01038	15			YL952-YL999, YN232-YR328
0662	16		PA		6-3		33-11-21	D46033J		18	16	TB3092W	A001	1		YC051-YD158, YN231
0662	16		PA		6-5		33-11-21	D46033J		18	16	TB3092W	A001	1		YL951-YL954, YN232-YN235
0662	16		PA		5-5		33-11-21	D46033J		18	16	TB3092W	A001	1		YL955-YL999, YN236-YR328
0663	16		PA		6-3		33-11-21	D46033J		26	16	TB3092W	A001	1		YC051-YD158, YN231

WIRE LIST

D280A108

91-21-11

Section W0000

Page 51

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To					
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W0003	286A0003				P3 - F/O INSTRUMENT PANEL (continued)											
0663	16		PA		6-5	33-11-21	D46033J		26	16		TB3092W	A001	1		YL951-YL954, YN232-YN235
0663	16		PA		5-5	33-11-21	D46033J		26	16		TB3092W	A001	1		YL955-YL999, YN236-YR328
0664	16		PA		5-2	33-11-21	D11842		2			D01038	19			YC051-YD158, YN231
0664	16		PA		5-3	33-11-21	D11842		2			D01038	19			YL951-YL999, YN232-YR328
0665	16		PA		5-3	33-11-21	D11842		4			TB3092W	A001	1		YC051-YD158, YN231
0665	16		PA		5-5	33-11-21	D11842		4			TB3092W	A001	1		YL951
0665	16		PA		5-2	33-11-21	D11842		4			TB3092W	A001	1		YL952-YL954, YN232-YN235
0665	16		PA		4-8	33-11-21	D11842		4			TB3092W	A001	1		YL955-YL999, YN236-YR328
0666	16		PA		5-3	33-11-21	D11842		3			TB3092W	B001	1		YC051-YD158, YN231
0666	16		PA		5-5	33-11-21	D11842		3			TB3092W	B001	1		YL951
0666	16		PA		5-2	33-11-21	D11842		3			TB3092W	B001	1		YL952-YL954, YN232-YN235
0666	16		PA		4-8	33-11-21	D11842		3			TB3092W	B001	1		YL955-YL999, YN236-YR328
0667	16		PA		4-9	33-11-21	D11842		1			GD00142	AC..	E		YC051-YD158, YL951, YN231
0667	16		PA		4-5	33-11-21	D11842		1			GD00142	AC..	E		YL952-YL999, YN232-YR328
0668	20		PA		4-9	33-11-21	D03991		1			TB3092W	B001	1		YC051-YD158, YN231
0668	20		PA		5-4	33-11-21	D03991		1			TB3092W	B001	1		YL951-YL954, YN232-YN235
0668	20		PA		4-11	33-11-21	D03991		1			TB3092W	B001	1		YL955-YL999, YN236-YR328
0669	20		PA		4-9	33-11-21	D03991		2			GD3010C	AC..	1A		YC051-YD158, YN231
0669	20		PA		5-2	33-11-21	D03991		2			GD3010C	AC..	1A		YL951-YL999, YN232-YR328
0670	20		PA		3-3	33-11-21	D00716		1			TB3092W	A005	1		YC051-YD158, YN231
0670	20		PA		2-8	33-11-21	D00716		1			TB3092W	A005	1		YL951
0670	20		PA		2-10	33-11-21	D00716		1			TB3092W	A005	1		YL952-YL954, YN232-YN235
0670	20		PA		2-11	33-11-21	D00716		1			TB3092W	A005	1		YL955-YL999, YN236-YR328
0671	20		PA		3-0	33-11-21	D00716		2			GD3010C	AC..	1A		YC051-YD158, YN231

WIRE LIST

D280A108

91-21-11

Section W0000

Page 52

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W0003	286A0003				P3 - F/O INSTRUMENT PANEL (continued)												
0671	20		PA		3-1	33-11-21		D00716			2		GD3010C	AC..	1A		YL951-YL954, YN232-YN235
0671	20		PA		2-7	33-11-21		D00716			2		GD3010C	AC..	1A		YL955-YL999, YN236-YR328
0674	14		PA		3-10	33-11-21		D01038			23		GD00142	AC..	E		YC051-YD158, YN231
0674	14		PA		3-9	33-11-21		D01038			23		GD00142	AC..	E		YL951
0674	14		PA		3-5	33-11-21		D01038			23		GD00142	AC..	E		YL952-YL999, YN232-YR328
0675	20		PA		4-3	33-11-21		D01038			1		TB3092W	B001	1		YC051-YD158, YN231
0675	20		PA		4-5	33-11-21		D01038			1		TB3092W	B001	1		YL951
0675	20		PA		4-2	33-11-21		D01038			1		TB3092W	B001	1		YL952-YL954, YN232-YN235
0675	20		PA		3-8	33-11-21		D01038			1		TB3092W	B001	1		YL955-YL999, YN236-YR328
0676	20		PA		4-4	33-11-21		D01038			2		GD3010C	AC..	1A		YC051-YD158, YN231
0676	20		PA		4-2	33-11-21		D01038			2		GD3010C	AC..	1A		YL951
0676	20		PA		3-11	33-11-21		D01038			2		GD3010C	AC..	1A		YL952-YL954, YN232-YN235
0676	20		PA		4-0	33-11-21		D01038			2		GD3010C	AC..	1A		YL955-YL999, YN236-YR328
0677	20		PA		4-8	33-11-21		D02678			1		TB3092W	B001	1		YC051-YD158, YL955-YN231, YN236-YR328
0677	20		PA		5-1	33-11-21		D02678			1		TB3092W	B001	1		YL951-YL954, YN232-YN235
0678	20		PA		4-8	33-11-21		D02678			2		GD3010C	AC..	1A		YC051-YD158, YN231
0678	20		PA		4-10	33-11-21		D02678			2		GD3010C	AC..	1A		YL951-YL954, YN232-YN235
0678	20		PA		4-11	33-11-21		D02678			2		GD3010C	AC..	1A		YL955-YL999, YN236-YR328
0679	20		PA		4-3	33-11-21		D01205			2		TB3092W	B001	1		YC051-YD158, YN231
0679	20		PA		4-4	33-11-21		D01205			2		TB3092W	B001	1		YL951
0679	20		PA		4-2	33-11-21		D01205			2		TB3092W	B001	1		YL952-YL954, YN232-YN235
0679	20		PA		3-8	33-11-21		D01205			2		TB3092W	B001	1		YL955-YL999, YN236-YR328
0680	20		PA		4-3	33-11-21		D01205			1		GD3010C	AC..	1A		YC051-YD158, YN231
0680	20		PA		4-2	33-11-21		D01205			1		GD3010C	AC..	1A		YL951

WIRE LIST

D280A108

91-21-11

Section W0000

Page 53

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To					
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W0003	286A0003				P3 - F/O INSTRUMENT PANEL (continued)												
0680	20		PA		3-11	33-11-21		D01205			1		GD3010C	AC..	1A		YL952-YL954, YN232-YN235
0680	20		PA		4-0	33-11-21		D01205			1		GD3010C	AC..	1A		YL955-YL999, YN236-YR328
0681	18		PA		1-7	31-62-21		D03995		4	18		GD00703	DC..	E		YC051-YD158
0681	18		PA		0-12	31-62-21		D03995		4	18		GD00703	DC..	E		YL951-YR328
0685	20		CQ		9-0	33-18-21		D00895		9			TB3092Y	A011	1A		YC051-YD158, YN231
0685	20		CQ		9-2	33-18-21		D00895		9			TB3092Y	A011	1A		YL951
0685	20		CQ		9-3	33-18-21		D00895		9			TB3092Y	A011	1A		YL952-YL954, YN232-YN235
0685	20		CQ		8-6	33-18-21		D00895		9			TB3092Y	A011	1A		YL955-YL999, YN236-YR328
0686	20		CQ		5-1	33-18-21		D00895		8			TB1092Y	A017	1A		YC051-YD158, YL955-YN231, YN236-YR328
0686	20		CQ		5-4	33-18-21		D00895		8			TB1092Y	A017	1A		YL951
0686	20		CQ		6-0	33-18-21		D00895		8			TB1092Y	A017	1A		YL952-YL954, YN232-YN235
0687	20		CQ		5-1	33-18-21		D00895		14			TB1092Y	B017	1A		YC051-YD158, YL955-YN231, YN236-YR328
0687	20		CQ		5-4	33-18-21		D00895		14			TB1092Y	B017	1A		YL951
0687	20		CQ		6-0	33-18-21		D00895		14			TB1092Y	B017	1A		YL952-YL954, YN232-YN235
0688	20		CQ		5-4	33-18-23		D40924J		11			TB3092Y	A015	1A		YC051-YD158, YN231
0688	20		CQ		6-1	33-18-23		D40924J		11			TB3092Y	A015	1A		YL951
0688	20		CQ		6-3	33-18-23		D40924J		11			TB3092Y	A015	1A		YL952-YL954, YN232-YN235
0688	20		CQ		5-1	33-18-23		D40924J		11			TB3092Y	A015	1A		YL955-YL999, YN236-YR328
0689	20		CQ		5-1	33-18-21		D00895		6			GD1010B	DC..	1A		YC051-YD158, YN231
0689	20		CQ		5-2	33-18-21		D00895		6			GD1010B	DC..	1A		YL951
0689	20		CQ		5-3	33-18-21		D00895		6			GD1010B	DC..	1A		YL952-YL954, YN232-YN235
0689	20		CQ		6-1	33-18-21		D00895		6			GD1010B	DC..	1A		YL955-YL999, YN236-YR328
0690	20		G5		9-4	33-18-21		D00895		3			D40824J	24			YC051-YD158, YN231
0690	20		G5		9-6	33-18-21		D00895		3			D40824J	24			YL951

WIRE LIST

D280A108

91-21-11

Section W0000

Page 54

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W0003	286A0003				P3 - F/O INSTRUMENT PANEL (continued)												
0690	20		G5		9-2	33-18-21		D00895		3			D40824J	24			YL952-YL999, YN232-YR328
0691	20		G5		9-6	33-18-21		D00895		11			D46033J	10			YC051-YD158, YN231
0691	20		G5		9-7	33-18-21		D00895		11			D46033J	10			YL951
0691	20		G5		9-3	33-18-21		D00895		11			D46033J	10			YL952-YL999, YN232-YR328
0692	20		CQ		4-5	33-18-22		D01205		12			TB3092Z	A021	1A		YC051-YD158, YN231
0692	20		CQ		4-8	33-18-22		D01205		12			TB3092Z	A021	1A		YL951
0692	20		CQ		4-7	33-18-22		D01205		12			TB3092Z	A021	1A		YL952-YL954, YN232-YN235
0692	20		CQ		4-0	33-18-22		D01205		12			TB3092Z	A021	1A		YL955-YL999, YN236-YR328
0693	20		CQ		4-5	33-18-22		D01205		11			TB3092Y	B015	1A		YC051-YD158, YN231
0693	20		CQ		4-7	33-18-22		D01205		11			TB3092Y	B015	1A		YL951-YL954, YN232-YN235
0693	20		CQ		3-11	33-18-22		D01205		11			TB3092Y	B015	1A		YL955-YL999, YN236-YR328
0694	20		CQ		5-4	33-18-22		D40924J		22			TB3092Y	B015	1A		YC051-YD158, YN231
0694	20		CQ		6-1	33-18-22		D40924J		22			TB3092Y	B015	1A		YL951
0694	20		CQ		6-3	33-18-22		D40924J		22			TB3092Y	B015	1A		YL952-YL954, YN232-YN235
0694	20		CQ		5-1	33-18-22		D40924J		22			TB3092Y	B015	1A		YL955-YL999, YN236-YR328
0695	20		CQ		4-10	33-18-22		D03991		5			TB3092Y	B015	1A		YC051-YD158, YN231
0695	20		CQ		6-1	33-18-22		D03991		5			TB3092Y	B015	1A		YL951
0695	20		CQ		6-4	33-18-22		D03991		5			TB3092Y	B015	1A		YL952-YL954, YN232-YN235
0695	20		CQ		5-1	33-18-22		D03991		5			TB3092Y	B015	1A		YL955-YL999, YN236-YR328
0696	20		CQ		4-10	33-18-22		D03991		3			TB3092Y	A013	1A		YC051-YD158, YN231
0696	20		CQ		6-1	33-18-22		D03991		3			TB3092Y	A013	1A		YL951
0696	20		CQ		6-4	33-18-22		D03991		3			TB3092Y	A013	1A		YL952-YL954, YN232-YN235
0696	20		CQ		5-1	33-18-22		D03991		3			TB3092Y	A013	1A		YL955-YL999, YN236-YR328
0697	20		CQ		4-7	33-18-22		D03991		4			GD3010B	DC..	1A		YC051-YD158, YN231
0697	20		CQ		5-0	33-18-22		D03991		4			GD3010B	DC..	1A		YL951
0697	20		CQ		5-1	33-18-22		D03991		4			GD3010B	DC..	1A		YL952-YL954, YN232-YN235

WIRE LIST

D280A108

91-21-11

Section W0000

Page 55

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0003	286A0003				P3 - F/O INSTRUMENT PANEL (continued)										
0697	20		CQ		5-2	33-18-22	D03991		4		GD3010B	DC..	1A		YL955-YL999, YN236-YR328
0698	20		CQ		3-1	33-18-22	D00716		10		TB3092Y	A013	1A		YC051-YD158, YN231
0698	20		CQ		2-5	33-18-22	D00716		10		TB3092Y	A013	1A		YL951
0698	20		CQ		2-8	33-18-22	D00716		10		TB3092Y	A013	1A		YL952-YL954, YN232-YN235
0698	20		CQ		2-10	33-18-22	D00716		10		TB3092Y	A013	1A		YL955-YL999, YN236-YR328
0699	20		CQ		6-6	33-18-24	D11732		26		TB3092Y	A011	1A		YC051-YD158, YN231
0699	20		CQ		6-9	33-18-24	D11732		26		TB3092Y	A011	1A		YL951
0699	20		CQ		7-1	33-18-24	D11732		26		TB3092Y	A011	1A		YL952-YL954, YN232-YN235
0699	20		CQ		6-4	33-18-24	D11732		26		TB3092Y	A011	1A		YL955-YL999, YN236-YR328
0700	20		CQ		6-8	33-18-24	D11732		14		TB3092Y	A013	1A		YC051-YD158, YN231
0700	20		CQ		6-11	33-18-24	D11732		14		TB3092Y	A013	1A		YL951
0700	20		CQ		7-2	33-18-24	D11732		14		TB3092Y	A013	1A		YL952-YL954, YN232-YN235
0700	20		CQ		6-6	33-18-24	D11732		14		TB3092Y	A013	1A		YL955-YL999, YN236-YR328
0701	20		CQ		6-5	33-18-24	D11732		5		GD3010B	DC..	1A		YC051-YD158, YL951-YL954, YN231-YN235
0701	20		CQ		6-6	33-18-24	D11732		5		GD3010B	DC..	1A		YL955-YL999, YN236-YR328
0702	20		CQ		6-7	33-18-24	D11732		20		TB3092Z	A021	1A		YC051-YD158, YL955-YN231, YN236-YR328
0702	20		CQ		7-1	33-18-24	D11732		20		TB3092Z	A021	1A		YL951-YL954, YN232-YN235
0703	20		CQ		6-5	33-18-24	D11732		8		GD3010B	DC..	1A		YC051-YD158, YL951-YL954, YN231-YN235
0703	20		CQ		6-6	33-18-24	D11732		8		GD3010B	DC..	1A		YL955-YL999, YN236-YR328
0704	20		CQ		6-8	33-18-24	D11732		21		TB3092Y	A015	1A		YC051-YD158, YN231
0704	20		CQ		6-11	33-18-24	D11732		21		TB3092Y	A015	1A		YL951
0704	20		CQ		7-2	33-18-24	D11732		21		TB3092Y	A015	1A		YL952-YL954, YN232-YN235

WIRE LIST

D280A108

91-21-11

Section W0000

Page 56

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0003	286A0003				P3 - F/O INSTRUMENT PANEL (continued)										
0704	20		CQ		6-6	33-18-24	D11732	21			TB3092Y	A015	1A		YL955-YL999, YN236-YR328
0705	20		CQ		6-2	33-18-51	D40824J	7			TB3092Y	B017	1A		YC051-YD158, YN231
0705	20		CQ		6-7	33-18-51	D40824J	7			TB3092Y	B017	1A		YL951-YL954, YN232-YN235
0705	20		CQ		6-1	33-18-51	D40824J	7			TB3092Y	B017	1A		YL955-YL999, YN236-YR328
0706	20		CQ		4-1	33-18-51	D40740J	21			TB3092Y	B017	1A		YC051-YD158, YN231
0706	20		CQ		3-8	33-18-51	D40740J	21			TB3092Y	B017	1A		YL951
0706	20		CQ		3-9	33-18-51	D40740J	21			TB3092Y	B017	1A		YL952-YL954, YN232-YN235
0706	20		CQ		5-0	33-18-51	D40740J	21			TB3092Y	B017	1A		YL955-YL999, YN236-YR328
0707	20		G5		9-6	22-13-11	D00895	10			D04251J	1			YC051-YD158, YN231
0707	20		G5		9-7	22-13-11	D00895	10			D04251J	1			YL951
0707	20		G5		9-3	22-13-11	D00895	10			D04251J	1			YL952-YL999, YN232-YR328
0708	22		G5		9-4	27-62-11	D00895	7			D40580J	2			YC051-YD158, YN231
0708	22		G5		9-5	27-62-11	D00895	7			D40580J	2			YL951
0708	22		G5		9-1	27-62-11	D00895	7			D40580J	2			YL952-YL999, YN232-YR328
0709	22		G5		9-4	27-62-11	D00895	5			D40580J	3			YC051-YD158, YN231
0709	22		G5		9-5	27-62-11	D00895	5			D40580J	3			YL951
0709	22		G5		9-1	27-62-11	D00895	5			D40580J	3			YL952-YL999, YN232-YR328
0710	22		PA		8-2	27-62-21	D03991	10			D40580J	1			YC051-YD158, YN231
0710	22		PA		8-8	27-62-21	D03991	10			D40580J	1			YL951
0710	22		PA		8-5	27-62-21	D03991	10			D40580J	1			YL952-YL999, YN232-YR328
0711	16		CQ		4-10	33-11-32	D11844	7			GD00142	AC..	E		YC051-YD158, YN231
0711	16		CQ		4-9	33-11-32	D11844	7			GD00142	AC..	E		YL951
0711	16		CQ		4-5	33-11-32	D11844	7			GD00142	AC..	E		YL952-YL999, YN232-YR328
0712	16		CQ		7-4	33-11-32	D11844	1			D40924J	2			YC051-YD158, YN231
0712	16		CQ		7-2	33-11-32	D11844	1			D40924J	2			YL951-YL999, YN232-YR328
0722	20		CQ		6-4	33-18-22	TB3092Z	A021	1A		TB1092Y	B017	1A		YC051-YD158, YN231
0722	20		CQ		6-11	33-18-22	TB3092Z	A021	1A		TB1092Y	B017	1A		YL951

WIRE LIST

D280A108

91-21-11

Section W0000

Page 57

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To					
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W0003	286A0003				P3 - F/O INSTRUMENT PANEL (continued)											
0722	20		CQ		7-1	33-18-22	TB3092Z		A021	1A		TB1092Y	B017	1A		YL952-YL954, YN232-YN235
0722	20		CQ		6-1	33-18-22	TB3092Z		A021	1A		TB1092Y	B017	1A		YL955-YL999, YN236-YR328
0723	20		CQ		6-4	33-18-22	TB3092Y		A013	1A		TB1092Y	A017	1A		YC051-YD158, YN231
0723	20		CQ		6-9	33-18-22	TB3092Y		A013	1A		TB1092Y	A017	1A		YL951
0723	20		CQ		7-1	33-18-22	TB3092Y		A013	1A		TB1092Y	A017	1A		YL952-YL954, YN232-YN235
0723	20		CQ		5-5	33-18-22	TB3092Y		A013	1A		TB1092Y	A017	1A		YL955-YL999, YN236-YR328
0732	16		PA		5-2	33-11-21	D11842			5		TB3092W	A005	1		YC051-YD158, YN231
0732	16		PA		5-5	33-11-21	D11842			5		TB3092W	A005	1		YL951
0732	16		PA		5-3	33-11-21	D11842			5		TB3092W	A005	1		YL952-YL954, YN232-YN235
0732	16		PA		4-9	33-11-21	D11842			5		TB3092W	A005	1		YL955-YL999, YN236-YR328
0743	24		G6		7-5	34-49-11	D01205			10		D04221J		45		YC053-YD158, YN231
0743	24		G6		7-3	34-49-11	D01205			10		D04221J		45		YL951
0743	24		G6		7-4	34-49-11	D01205			10		D04221J		45		YL952-YL999, YN232-YR328
0750	24		G6		7-4	34-49-11	D01205		CAP	Y		D04221J		18		YL956-YL999, YN236-YR328
0751	24		G6		7-4	34-49-11	D01205		CAP	Y		D04221J		19		YL956-YL999, YN236-YR328
1501	16		X1	YA	6-3	31-62-21	D03985B			59		D46033J		15		YC051-YD158, YN231
1501	16		X1	YA	6-6	31-62-21	D03985B			59		D46033J		15		YL951-YL954, YN232-YN235
1501	16		X1	YA	6-4	31-62-21	D03985B			59		D46033J		15		YL955-YL999, YN236-YR328
1501Z				YA	0-0	31-62-21	D03985B		PERG	1A		D46033J		S/R		YC051-YD158, YL951-YR328
1502	16		X1	YB	5-0	31-62-21	D03987B			59		D46033J		19		YC051-YD158, YN231
1502	16		X1	YB	5-4	31-62-21	D03987B			59		D46033J		19		YL951
1502	16		X1	YB	5-2	31-62-21	D03987B			59		D46033J		19		YL952-YL999, YN232-YR328
1502Z				YB	0-0	31-62-21	D03987B		PERG	1A		D46033J		S/R		YC051-YD158, YL951-YR328
1503	16		X1	YC	6-0	31-62-21	D03983B			59		D46033J		23		YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0000

Page 58

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	FT-IN	Diagram	From			To			Effectivity	
	GA	CO	TY				Equip	Term	Type	Splice	Equip	Term		Type
W0003	286A0003			P3 - F/O INSTRUMENT PANEL (continued)										
1503Z				YC	0-0	31-62-21	D03983B	PERG	1A		D46033J	S/R		YC051-YD158, YL951-YR328
1504	22	X1	YD		8-6	31-62-21	D03995		3		D46033J	12		YC051-YD158, YN231
1504	22	X1	YD		8-5	31-62-21	D03995		3		D46033J	12		YL951
1504	22	X1	YD		8-1	31-62-21	D03995		3		D46033J	12		YL952-YL999, YN232-YR328
1504Z				YD	0-0	31-62-21	D03995	S/R			D46033J	S/R		YC051-YD158, YL951-YR328
1505	24	Y1	YE		9-1	31-62-23	D00333		52		D03995	49		YC051-YD158, YN231
1505	24	Y1	YE		8-10	31-62-23	D00333		52		D03995	49		YL951
1505	24	Y1	YE		8-7	31-62-23	D00333		52		D03995	49		YL952-YL999, YN232-YR328
1505Z				YE	0-0	31-62-23	D00333	S/R			D03995	S/R		YC051-YD158, YL951-YR328
1506	24	Y1	YF		9-1	31-62-23	D00333		53		D03995	37		YC051-YD158, YN231
1506	24	Y1	YF		8-10	31-62-23	D00333		53		D03995	37		YL951
1506	24	Y1	YF		8-7	31-62-23	D00333		53		D03995	37		YL952-YL999, YN232-YR328
1506Z				YF	0-0	31-62-23	D00333	S/R			D03995	S/R		YC051-YD158, YL951-YR328
1507	24	Y1	YG		9-1	31-62-23	D00333		54		D03995	11		YC051-YD158, YN231
1507	24	Y1	YG		8-10	31-62-23	D00333		54		D03995	11		YL951
1507	24	Y1	YG		8-7	31-62-23	D00333		54		D03995	11		YL952-YL999, YN232-YR328
1507Z				YG	0-0	31-62-23	D00333	S/R			D03995	S/R		YC051-YD158, YL951-YR328
1508	24	Y1	YH		9-1	31-62-23	D00333		55		D03995	16		YC051-YD158, YN231
1508	24	Y1	YH		8-10	31-62-23	D00333		55		D03995	16		YL951
1508	24	Y1	YH		8-7	31-62-23	D00333		55		D03995	16		YL952-YL999, YN232-YR328
1508Z				YH	0-0	31-62-23	D00333	S/R			D03995	S/R		YC051-YD158, YL951-YR328
1509	20	X1	YI		4-11	33-11-21	D03995		1		TB3092W	A001	1	YC051-YD158, YL952-YL954, YN231-YN235
1509	20	X1	YI		4-10	33-11-21	D03995		1		TB3092W	A001	1	YL951
1509	20	X1	YI		4-5	33-11-21	D03995		1		TB3092W	A001	1	YL955-YL999, YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W0000

Page 59

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0003	286A0003			P3 - F/O INSTRUMENT PANEL (continued)											
1509Z				YI	0-0	33-11-21	D03995		S/R		GD3010A	ST..	1		YC051-YD158, YL951-YR328
1510	20	X1	YJ		4-11	33-11-21	D03995		2		GD3010C	AC..	1A		YC051-YD158, YN231
1510	20	X1	YJ		4-8	33-11-21	D03995		2		GD3010C	AC..	1A		YL951-YL999, YN232-YR328
1510Z				YJ	0-0	33-11-21	D03995		S/R		GD3010C	ST..	1A		YC051-YD158, YL951-YR328
1514R	22	X5	YN		9-1	26-11-21	D40740J		14		TB0101Y	B019	1A		YC051-YD158, YN231
1514R	22	X5	YN		8-7	26-11-21	D40740J		14		TB0101Y	B019	1A		YL951
1514R	22	X5	YN		8-8	26-11-21	D40740J		14		TB0101Y	B019	1A		YL952-YL954, YN232-YN235
1514R	22	X5	YN		8-2	26-11-21	D40740J		14		TB0101Y	B019	1A		YL955-YL999, YN236-YR328
1514Z				YN	0-0	26-11-21	D40740J		DED		TB0101Y		DED		YC051-YD158, YL951-YR328
1515R	22	X5	YO		9-2	26-11-21	D40740J		15		TB0101Z	B021	1A		YC051-YD158, YN231
1515R	22	X5	YO		8-7	26-11-21	D40740J		15		TB0101Z	B021	1A		YL951-YL954, YN232-YN235
1515R	22	X5	YO		8-2	26-11-21	D40740J		15		TB0101Z	B021	1A		YL955-YL999, YN236-YR328
1515Z				YO	0-0	26-11-21	D40740J		DED		TB0101Z		DED		YC051-YD158, YL951-YR328
1516R	22	X5	YP		9-2	26-11-21	D40740J		16		TB0101Z	B021	1A		YC051-YD158, YN231
1516R	22	X5	YP		8-7	26-11-21	D40740J		16		TB0101Z	B021	1A		YL951-YL954, YN232-YN235
1516R	22	X5	YP		8-2	26-11-21	D40740J		16		TB0101Z	B021	1A		YL955-YL999, YN236-YR328
1516Z				YP	0-0	26-11-21	D40740J		DED		TB0101Z		DED		YC051-YD158, YL951-YR328
201CO				ZA	0-0	31-62-22	D03985A		= 2T		D10045		= C1		YC051-YD158, YL951-YR328
201CX				0F ZA	3-5	31-62-22	D03985A		2T		D10045		= A1		YC051-YD158, YL955-YN231, YN236-YR328
201CX				0F ZA	3-4	31-62-22	D03985A		2T		D10045		= A1		YL951-YL954, YN232-YN235
202CO				ZB	0-0	31-62-22	D03987A		= 2T		D10047		= C1		YC051-YD158, YL951-YR328
202CX				0F ZB	2-11	31-62-22	D03987A		2T		D10047		= A1		YC051-YD158, YN231

WIRE LIST

D280A108

91-21-11

Section W0000

Page 60

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W0003	286A0003			P3 - F/O INSTRUMENT PANEL (continued)										
202CX			0F	ZB	2-9	31-62-22	D03987A	2T		D10047	= A1		YL951-YL999, YN232-YR328	
203CO				ZC	0-0	31-62-22	D03983A	= 2T		D10049	= C1		YC051-YD158, YL951-YR328	
203CX			0F	ZC	4-4	31-62-22	D03983A	2T		D10049	= A1		YC051-YD158, YN231	
203CX			0F	ZC	3-10	31-62-22	D03983A	2T		D10049	= A1		YL951	
203CX			0F	ZC	3-9	31-62-22	D03983A	2T		D10049	= A1		YL952-YL999, YN232-YR328	
204CO				ZD	0-0	31-62-22	D03981A	= 2T		D10051	= C1		YC051-YD158, YL951-YR328	
204CX			0F	ZD	3-6	31-62-22	D03981A	2T		D10051	= A1		YC051-YD158, YN231	
204CX			0F	ZD	3-5	31-62-22	D03981A	2T		D10051	= A1		YL951	
204CX			0F	ZD	3-2	31-62-22	D03981A	2T		D10051	= A1		YL952-YL999, YN232-YR328	
205CO				ZE	0-0	31-62-22	D03979A	= 2T		D10053	= C1		YC051-YD158, YL951-YR328	
205CX			0F	ZE	4-4	31-62-22	D03979A	2T		D10053	= A1		YC051-YD158, YN231	
205CX			0F	ZE	4-3	31-62-22	D03979A	2T		D10053	= A1		YL951	
205CX			0F	ZE	4-0	31-62-22	D03979A	2T		D10053	= A1		YL952-YL999, YN232-YR328	
206CO				ZF	0-0	31-62-22	D03977A	= 2T		D10055	= C1		YC051-YD158, YL951-YR328	
206CX			0F	ZF	4-9	31-62-22	D03977A	2T		D10055	= A1		YC051-YD158, YL951, YN231	
206CX			0F	ZF	4-7	31-62-22	D03977A	2T		D10055	= A1		YL952-YL999, YN232-YR328	
2501B	24		Y2	AA	2-6	31-62-21	D03985B	E04		TB0301Y	B011	1A	YC051-YD158, YN231	
2501B	24		Y2	AA	2-8	31-62-21	D03985B	E04		TB0301Y	B011	1A	YL951	
2501B	24		Y2	AA	2-9	31-62-21	D03985B	E04		TB0301Y	B011	1A	YL952-YL954, YN232-YN235	
2501B	24		Y2	AA	2-5	31-62-21	D03985B	E04		TB0301Y	B011	1A	YL955-YL999, YN236-YR328	
2501R	24		Y2	AA	0-0	31-62-21	D03985B	E03		TB0301Y	A011	1A	YC051-YD158, YL951-YR328	
2501Z				AA	0-0	31-62-21	D03985B	PERG	1A	GB00301	ST..	1A	YC051-YD158, YL951-YR328	
2502B	24		Y2	AB	5-4	31-62-22	D03983B	A04		D04237J	4		YC051-YD158, YN231	
2502B	24		Y2	AB	5-3	31-62-22	D03983B	A04		D04237J	4		YL951-YL999, YN232-YR328	

WIRE LIST

D280A108

91-21-11

Section W0000

Page 61

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Description Fam FT-IN Diagram		From Equip Term Type Splice				To Equip Term Type Splice Effectivity				
W0003	286A0003			P3 - F/O INSTRUMENT PANEL (continued)										
2502R	24	Y2	AB	0-0	31-62-22	D03983B	A03			D04237J	3		YC051-YD158, YL951-YR328	
2502Z			AB	0-0	31-62-22	D03983B	PERG	1A		D04237J	S/R		YC051-YD158, YL951-YR328	
2503B	24	Y2	AC	6-0	31-62-22	D03985B	A04			D04237J	2		YC051-YD158, YN231	
2503B	24	Y2	AC	6-3	31-62-22	D03985B	A04			D04237J	2		YL951-YL954, YN232-YN235	
2503B	24	Y2	AC	6-1	31-62-22	D03985B	A04			D04237J	2		YL955-YL999, YN236-YR328	
2503R	24	Y2	AC	0-0	31-62-22	D03985B	A03			D04237J	1		YC051-YD158, YL951-YR328	
2503Z			AC	0-0	31-62-22	D03985B	PERG	1A		D04237J	S/R		YC051-YD158, YL951-YR328	
2504B	24	Y2	AD	5-0	31-62-22	D03987B	A04			D04251J	14		YC051-YD158, YN231	
2504B	24	Y2	AD	5-4	31-62-22	D03987B	A04			D04251J	14		YL951	
2504B	24	Y2	AD	5-2	31-62-22	D03987B	A04			D04251J	14		YL952-YL999, YN232-YR328	
2504R	24	Y2	AD	0-0	31-62-22	D03987B	A03			D04251J	13		YC051-YD158, YL951-YR328	
2504Z			AD	0-0	31-62-22	D03987B	PERG	1A		D04251J	S/R		YC051-YD158, YL951-YR328	
2505B	24	Y2	AE	4-11	31-62-23	D03995	36			TB0301Y	B001	1A	YC051-YD158, YN231	
2505B	24	Y2	AE	4-9	31-62-23	D03995	36			TB0301Y	B001	1A	YL951	
2505B	24	Y2	AE	4-10	31-62-23	D03995	36			TB0301Y	B001	1A	YL952-YL954, YN232-YN235	
2505B	24	Y2	AE	4-5	31-62-23	D03995	36			TB0301Y	B001	1A	YL955-YL999, YN236-YR328	
2505R	24	Y2	AE	0-0	31-62-23	D03995	35			TB0301Y	A001	1A	YC051-YD158, YL951-YR328	
2505Z			AE	0-0	31-62-23	D03995	S/R			GB00301	ST..	1A	YC051-YD158, YL951-YR328	
2506B	24	Y2	AF	6-1	31-62-23	D04237J	10			TB0301Y	B001	1A	YC051-YD158, YL951, YN231	
2506B	24	Y2	AF	6-2	31-62-23	D04237J	10			TB0301Y	B001	1A	YL952-YL954, YN232-YN235	
2506B	24	Y2	AF	5-2	31-62-23	D04237J	10			TB0301Y	B001	1A	YL955-YL999, YN236-YR328	
2506R	24	Y2	AF	0-0	31-62-23	D04237J	9			TB0301Y	A001	1A	YC051-YD158, YL951-YR328	

WIRE LIST
D280A108

91-21-11
Section W0000
Page 62
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W0003	286A0003			P3 - F/O INSTRUMENT PANEL (continued)										
2506Z				AF	0-0	31-62-23	D04237J	S/R		GB00301	ST..	1A		YC051-YD158, YL951-YR328
2507B	24	Y2	AG		6-1	31-62-23	D04237J	12		TB0301Y	B001	1A		YC051-YC052
2507R	24	Y2	AG		0-0	31-62-23	D04237J	11		TB0301Y	A001	1A		YC051-YC052
2507Z			AG		0-0	31-62-23	D04237J	S/R		GB00301	ST..	1A		YC051-YC052
2509B	24	Y2	AI		8-7	31-22-11	D00716	23		D04221J		36		YC051-YD158, YN231
2509B	24	Y2	AI		8-5	31-22-11	D00716	23		D04221J		36		YL951
2509B	24	Y2	AI		8-4	31-22-11	D00716	23		D04221J		36		YL952-YL954, YN232-YN235
2509B	24	Y2	AI		8-2	31-22-11	D00716	23		D04221J		36		YL955-YL999, YN236-YR328
2509R	24	Y2	AI		0-0	31-22-11	D00716	24		D04221J		35		YC051-YD158, YL951-YR328
2509Z			AI		0-0	31-22-11	D00716	DED		D04221J	S/R			YC051-YC052
2509Z			AI		0-0	31-22-11	D00716	S/R		D04221J	S/R			YC053-YD158, YL951-YR328
2510B	24	Y2	AJ		4-3	31-62-21	D40740J	26		TB0301Y	B011	1A		YC051-YD158, YN231
2510B	24	Y2	AJ		3-4	31-62-21	D40740J	26		TB0301Y	B011	1A		YL951
2510B	24	Y2	AJ		3-7	31-62-21	D40740J	26		TB0301Y	B011	1A		YL952-YL954, YN232-YN235
2510B	24	Y2	AJ		4-10	31-62-21	D40740J	26		TB0301Y	B011	1A		YL955-YL999, YN236-YR328
2510R	24	Y2	AJ		0-0	31-62-21	D40740J	25		TB0301Y	A011	1A		YC051-YD158, YL951-YR328
2510Z			AJ		0-0	31-62-21	D40740J	S/R		GB00301	ST..	1A		YC051-YD158, YL951-YR328
2511B	24	Y2	AK		6-4	31-62-21	D04251J	18		TB0301Y	B011	1A		YC051-YD158, YN231
2511B	24	Y2	AK		6-5	31-62-21	D04251J	18		TB0301Y	B011	1A		YL951
2511B	24	Y2	AK		6-7	31-62-21	D04251J	18		TB0301Y	B011	1A		YL952-YL954, YN232-YN235
2511B	24	Y2	AK		6-0	31-62-21	D04251J	18		TB0301Y	B011	1A		YL955-YL999, YN236-YR328
2511R	24	Y2	AK		0-0	31-62-21	D04251J	17		TB0301Y	A011	1A		YC051-YD158, YL951-YR328
2511Z			AK		0-0	31-62-21	D04251J	S/R		GB00301	ST..	1A		YC051-YD158, YL951-YR328
2512B	24	Y2	AL		3-11	31-62-23	D03991	23		D03995		44		YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0000

Page 63

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY	Description Fam	Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W0003	286A0003	P3 - F/O INSTRUMENT PANEL (continued)										
2512R	24	Y2	AL	0-0	31-62-23	D03991	24	D03995	25			YC051-YD158, YL951-YR328
2512Z			AL	0-0	31-62-23	D03991	S/R	D03995	S/R			YC051-YD158, YL951-YR328
2513B	24	Y2	AM	9-1	31-62-23	D00333	21	D03995	55			YC051-YD158, YN231
2513B	24	Y2	AM	8-10	31-62-23	D00333	21	D03995	55			YL951
2513B	24	Y2	AM	8-7	31-62-23	D00333	21	D03995	55			YL952-YL999, YN232-YR328
2513R	24	Y2	AM	0-0	31-62-23	D00333	22	D03995	18			YC051-YD158, YL951-YR328
2513Z			AM	0-0	31-62-23	D00333	S/R	D03995	S/R			YC051-YD158, YL951-YR328
2514B	24	Y2	AN	11-2	31-62-23	D00895	23	D03995	53			YC051-YD158, YN231
2514B	24	Y2	AN	11-1	31-62-23	D00895	23	D03995	53			YL951
2514B	24	Y2	AN	10-7	31-62-23	D00895	23	D03995	53			YL952-YL999, YN232-YR328
2514R	24	Y2	AN	0-0	31-62-23	D00895	24	D03995	34			YC051-YD158, YL951-YR328
2514Z			AN	0-0	31-62-23	D00895	S/R	D03995	S/R			YC051-YD158, YL951-YR328
2515B	24	Y2	AP	6-8	29-32-11	D40578J	13	GD0301B	DC..	1A		YC051-YD158, YL951-YL954, YN231-YN235
2515B	24	Y2	AP	7-0	29-32-11	D40578J	13	GD0301B	DC..	1A		YL955-YL999, YN236-YR328
2515R	24	Y2	AP	0-0	29-32-11	D40578J	12	SM00501		W		YC051-YD158, YL951-YR328
2515Z			AP	0-0	29-32-11	D40578J	S/R	GD0301B	ST..	1A		YC051-YD158, YL951-YR328
2516B	24	Y2	AQ	3-9	29-32-11	GD0301B	DC..	D02678	4			YC051-YD158, YN231
2516B	24	Y2	AQ	4-10	29-32-11	GD0301B	DC..	D02678	4			YL951-YL954, YN232-YN235
2516B	24	Y2	AQ	5-2	29-32-11	GD0301B	DC..	D02678	4			YL955-YL999, YN236-YR328
2516R	24	Y2	AQ	0-0	29-32-11	SM00501		D02678	5			YC051-YD158, YL951-YR328
2516Z			AQ	0-0	29-32-11	GD0301B	ST..	D02678	S/R			YC051-YD158, YL951-YR328
2517B	24	Y2	AR	8-0	34-58-21	D04251J	16	D00716	20	VP		YC053

WIRE LIST

D280A108

91-21-11

Section W0000

Page 64

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0003	286A0003			P3 - F/O INSTRUMENT PANEL (continued)											
2517B	24	Y2	AR	8-0	34-58-21	D04251J	16			D00716	20			YC054-YD158, YN231	
2517B	24	Y2	AR	7-9	34-58-21	D04251J	16			D00716	20			YL951	
2517B	24	Y2	AR	7-8	34-58-21	D04251J	16			D00716	20			YL952-YL954, YN232-YN235	
2517B	24	Y2	AR	7-6	34-58-21	D04251J	16			D00716	20			YL955-YL999, YN236-YR328	
2517R	24	Y2	AR	0-0	34-58-21	D04251J	15			D00716	19	VP		YC053	
2517R	24	Y2	AR	0-0	34-58-21	D04251J	15			D00716	19			YC054-YD158, YL951-YR328	
2517Z			AR	0-0	34-58-21	D04251J	S/R			D00716	DED			YC053	
2517Z			AR	0-0	34-58-21	D04251J	S/R			D00716	S/R			YC054-YD158, YL951-YR328	
301CO			ZM	0-0	31-62-42	D03987A	=9T			D10032P	=C1			YL951, YN231	
301CO			ZM	0-0	31-62-42	D03987A	=9T			D10032J	=C1			YL952-YL999, YN232-YR328	
301CX		0F	ZM	10-5	31-62-42	D03987A	9T			D10032P	=A1			YL951, YN231	
301CX		0F	ZM	4-8	31-62-42	D03987A	9T			D10032J	=A1			YL952-YL999, YN232-YR328	
302CO			ZN	0-0	31-62-42	D03983A	=9T			D10034P	=C1			YL951, YN231	
302CO			ZN	0-0	31-62-42	D03983A	=9T			D10034J	=C1			YL952-YL999, YN232-YR328	
302CX		0F	ZN	10-6	31-62-42	D03983A	9T			D10034P	=A1			YL951	
302CX		0F	ZN	4-8	31-62-42	D03983A	9T			D10034J	=A1			YL952-YL999, YN232-YR328	
302CX		0F	ZN	10-7	31-62-42	D03983A	9T			D10034P	=A1			YN231	
3501B	24	Y3	XA	5-2	31-62-21	D03985B	D03			D40740J	23			YC051-YD158, YL955-YN231, YN236-YR328	
3501B	24	Y3	XA	4-9	31-62-21	D03985B	D03			D40740J	23			YL951	
3501B	24	Y3	XA	4-7	31-62-21	D03985B	D03			D40740J	23			YL952-YL954, YN232-YN235	
3501R	24	Y3	XA	0-0	31-62-21	D03985B	C03			D40740J	22			YC051-YD158, YL951-YR328	
3501Y	24	Y3	XA	0-0	31-62-21	D03985B	C04			D40740J	24			YC051-YD158, YL951-YR328	
3501Z			XA	0-0	31-62-21	D03985B	PERG	1A		D40740J	S/R			YC051-YD158, YL951-YR328	
3502B	24	Y3	XB	3-11	31-62-23	D03991	15			D03995	42			YC051-YD158, YL951-YR328	

WIRE LIST

D280A108

91-21-11

Section W0000

Page 65

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0003	286A0003				P3 - F/O INSTRUMENT PANEL (continued)										
3502R	24		Y3	XB	0-0	31-62-23	D03991	18			D03995	41			YC051-YD158, YL951-YR328
3502Y	24		Y3	XB	0-0	31-62-23	D03991	16			D03995	43			YC051-YD158, YL951-YR328
3502Z				XB	0-0	31-62-23	D03991	S/R			D03995	S/R			YC051-YD158, YL951-YR328
3503B	24		Y3	XC	3-11	31-62-23	D03991	20			D03995	23			YC051-YD158, YL951-YR328
3503R	24		Y3	XC	0-0	31-62-23	D03991	21			D03995	22			YC051-YD158, YL951-YR328
3503Y	24		Y3	XC	0-0	31-62-23	D03991	19			D03995	24			YC051-YD158, YL951-YR328
3503Z				XC	0-0	31-62-23	D03991	S/R			D03995	S/R			YC051-YD158, YL951-YR328
3504B	24		Y3	XD	9-1	31-62-23	D00333	6			D03995	47			YC051-YD158, YN231
3504B	24		Y3	XD	8-10	31-62-23	D00333	6			D03995	47			YL951
3504B	24		Y3	XD	8-7	31-62-23	D00333	6			D03995	47			YL952-YL999, YN232-YR328
3504R	24		Y3	XD	0-0	31-62-23	D00333	5			D03995	46			YC051-YD158, YL951-YR328
3504Y	24		Y3	XD	0-0	31-62-23	D00333	7			D03995	48			YC051-YD158, YL951-YR328
3504Z				XD	0-0	31-62-23	D00333	S/R			D03995	S/R			YC051-YD158, YL951-YR328
3505B	24		Y3	XE	9-1	31-62-23	D00333	10			D03995	28			YC051-YD158, YN231
3505B	24		Y3	XE	8-10	31-62-23	D00333	10			D03995	28			YL951
3505B	24		Y3	XE	8-7	31-62-23	D00333	10			D03995	28			YL952-YL999, YN232-YR328
3505R	24		Y3	XE	0-0	31-62-23	D00333	11			D03995	27			YC051-YD158, YL951-YR328
3505Y	24		Y3	XE	0-0	31-62-23	D00333	9			D03995	29			YC051-YD158, YL951-YR328
3505Z				XE	0-0	31-62-23	D00333	S/R			D03995	S/R			YC051-YD158, YL951-YR328
3506B	24		Y3	XF	9-1	31-62-23	D00333	15			D03995	39			YC051-YD158, YN231
3506B	24		Y3	XF	8-10	31-62-23	D00333	15			D03995	39			YL951
3506B	24		Y3	XF	8-7	31-62-23	D00333	15			D03995	39			YL952-YL999, YN232-YR328

WIRE LIST
D280A108

91-21-11
Section W0000
Page 66
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0003	286A0003			P3 - F/O INSTRUMENT PANEL (continued)											
3506R	24	Y3	XF		0-0	31-62-23	D00333		14		D03995		38		YC051-YD158, YL951-YR328
3506Y	24	Y3	XF		0-0	31-62-23	D00333		16		D03995		40		YC051-YD158, YL951-YR328
3506Z			XF		0-0	31-62-23	D00333		S/R		D03995		S/R		YC051-YD158, YL951-YR328
3507B	24	Y3	XG		9-1	31-62-23	D00333		19		D03995		9		YC051-YD158, YN231
3507B	24	Y3	XG		8-10	31-62-23	D00333		19		D03995		9		YL951
3507B	24	Y3	XG		8-7	31-62-23	D00333		19		D03995		9		YL952-YL999, YN232-YR328
3507R	24	Y3	XG		0-0	31-62-23	D00333		18		D03995		8		YC051-YD158, YL951-YR328
3507Y	24	Y3	XG		0-0	31-62-23	D00333		20		D03995		19		YC051-YD158, YL951-YR328
3507Z			XG		0-0	31-62-23	D00333		S/R		D03995		S/R		YC051-YD158, YL951-YR328
3508B	24	Y3	XH		11-2	31-62-23	D00895		15		D03995		51		YC051-YD158, YN231
3508B	24	Y3	XH		11-1	31-62-23	D00895		15		D03995		51		YL951
3508B	24	Y3	XH		10-7	31-62-23	D00895		15		D03995		51		YL952-YL999, YN232-YR328
3508R	24	Y3	XH		0-0	31-62-23	D00895		16		D03995		50		YC051-YD158, YL951-YR328
3508Y	24	Y3	XH		0-0	31-62-23	D00895		18		D03995		52		YC051-YD158, YL951-YR328
3508Z			XH		0-0	31-62-23	D00895		S/R		D03995		S/R		YC051-YD158, YL951-YR328
3509B	24	Y3	XJ		11-2	31-62-23	D00895		20		D03995		32		YC051-YD158, YN231
3509B	24	Y3	XJ		11-1	31-62-23	D00895		20		D03995		32		YL951
3509B	24	Y3	XJ		10-7	31-62-23	D00895		20		D03995		32		YL952-YL999, YN232-YR328
3509R	24	Y3	XJ		0-0	31-62-23	D00895		21		D03995		31		YC051-YD158, YL951-YR328
3509Y	24	Y3	XJ		0-0	31-62-23	D00895		19		D03995		33		YC051-YD158, YL951-YR328
3509Z			XJ		0-0	31-62-23	D00895		S/R		D03995		S/R		YC051-YD158, YL951-YR328
3511B	24	Y3	XL		4-4	31-62-21	D03985B		J01		D01038		7		YC051-YD158, YN231
3511B	24	Y3	XL		4-5	31-62-21	D03985B		J01		D01038		7		YL951

WIRE LIST

D280A108

91-21-11

Section W0000

Page 67

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0003	286A0003				P3 - F/O INSTRUMENT PANEL (continued)										
3511B	24	Y3	XL		4-3	31-62-21	D03985B	J01			D01038	7			YL952-YL954, YN232-YN235
3511B	24	Y3	XL		4-1	31-62-21	D03985B	J01			D01038	7			YL955-YL999, YN236-YR328
3511R	24	Y3	XL		0-0	31-62-21	D03985B	J02			D01038	6			YC051-YD158, YL951-YR328
3511Y	24	Y3	XL		0-0	31-62-21	D03985B	J03			D01038	8			YC051-YD158, YL951-YR328
3511Z			XL		0-0	31-62-21	D03985B	PERG	1A		D01038	S/R			YC051-YD158, YL951-YR328
3512B	24	Y3	XM		3-7	31-62-21	D03987B	J01			D01038	10			YC051-YD158, YN231
3512B	24	Y3	XM		3-10	31-62-21	D03987B	J01			D01038	10			YL951
3512B	24	Y3	XM		3-9	31-62-21	D03987B	J01			D01038	10			YL952-YL999, YN232-YR328
3512R	24	Y3	XM		0-0	31-62-21	D03987B	J02			D01038	9			YC051-YD158, YL951-YR328
3512Y	24	Y3	XM		0-0	31-62-21	D03987B	J03			D01038	11			YC051-YD158, YL951-YR328
3512Z			XM		0-0	31-62-21	D03987B	PERG	1A		D01038	S/R			YC051-YD158, YL951-YR328
3513B	24	Y3	XN		3-7	31-62-21	D03987B	H01			D01038	13			YC051-YD158, YN231
3513B	24	Y3	XN		3-10	31-62-21	D03987B	H01			D01038	13			YL951
3513B	24	Y3	XN		3-9	31-62-21	D03987B	H01			D01038	13			YL952-YL999, YN232-YR328
3513R	24	Y3	XN		0-0	31-62-21	D03987B	H02			D01038	12			YC051-YD158, YL951-YR328
3513Y	24	Y3	XN		0-0	31-62-21	D03987B	H03			D01038	14			YC051-YD158, YL951-YR328
3513Z			XN		0-0	31-62-21	D03987B	PERG	1A		D01038	S/R			YC051-YD158, YL951-YR328
3514B	24	Y3	XO		7-4	31-62-21	D03983B	J01			D02650	21			YC051-YD158, YN231
3514B	24	Y3	XO		7-2	31-62-21	D03983B	J01			D02650	21			YL951
3514B	24	Y3	XO		7-0	31-62-21	D03983B	J01			D02650	21			YL952-YL999, YN232-YR328
3514R	24	Y3	XO		0-0	31-62-21	D03983B	J02			D02650	20			YC051-YD158, YL951-YR328
3514Y	24	Y3	XO		0-0	31-62-21	D03983B	J03			D02650	22			YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0000

Page 68

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W0003	286A0003			P3 - F/O INSTRUMENT PANEL (continued)										
3514Z				XO	0-0	31-62-21	D03983B	PERG	1A		D02650	S/R		YC051-YD158, YL951-YR328
3515B	24	Y3	XP		7-4	31-62-21	D03983B	H01			D02650	25		YC051-YD158, YN231
3515B	24	Y3	XP		7-2	31-62-21	D03983B	H01			D02650	25		YL951
3515B	24	Y3	XP		7-0	31-62-21	D03983B	H01			D02650	25		YL952-YL999, YN232-YR328
3515R	24	Y3	XP		0-0	31-62-21	D03983B	H02			D02650	24		YC051-YD158, YL951-YR328
3515Y	24	Y3	XP		0-0	31-62-21	D03983B	H03			D02650	26		YC051-YD158, YL951-YR328
3515Z				XP	0-0	31-62-21	D03983B	PERG	1A		D02650	S/R		YC051-YD158, YL951-YR328
401CO				ZG	0-0	31-62-22	D03985A	=3T			D10073	=C1		YC051-YD158, YL951-YR328
401CX		0F	ZG		3-6	31-62-22	D03985A	3T			D10073	=A1		YC051-YD158, YN231
401CX		0F	ZG		3-3	31-62-22	D03985A	3T			D10073	=A1		YL951
401CX		0F	ZG		3-4	31-62-22	D03985A	3T			D10073	=A1		YL952-YL999, YN232-YR328
402CO				ZH	0-0	31-62-22	D03987A	=3T			D10075	=C1		YC051-YD158, YL951-YR328
402CX		0F	ZH		3-0	31-62-22	D03987A	3T			D10075	=A1		YC051-YD158, YN231
402CX		0F	ZH		2-8	31-62-22	D03987A	3T			D10075	=A1		YL951
402CX		0F	ZH		2-9	31-62-22	D03987A	3T			D10075	=A1		YL952-YL999, YN232-YR328
403CO				ZI	0-0	31-62-22	D03983A	=3T			D10077	=C1		YC051-YD158, YL951-YR328
403CX		0F	ZI		4-5	31-62-22	D03983A	3T			D10077	=A1		YC051-YD158, YN231
403CX		0F	ZI		4-0	31-62-22	D03983A	3T			D10077	=A1		YL951-YL999, YN232-YR328
404CO				ZJ	0-0	31-62-22	D03981A	=3T			D10079	=C1		YC051-YD158, YL951-YR328
404CX		0F	ZJ		3-7	31-62-22	D03981A	3T			D10079	=A1		YC051-YD158, YN231
404CX		0F	ZJ		3-4	31-62-22	D03981A	3T			D10079	=A1		YL951
404CX		0F	ZJ		3-1	31-62-22	D03981A	3T			D10079	=A1		YL952-YL999, YN232-YR328
405CO				ZK	0-0	31-62-22	D03979A	=3T			D10081	=C1		YC051-YD158, YL951-YR328
405CX		0F	ZK		4-6	31-62-22	D03979A	3T			D10081	=A1		YC051-YD158, YN231
405CX		0F	ZK		4-2	31-62-22	D03979A	3T			D10081	=A1		YL951

WIRE LIST

D280A108

91-21-11

Section W0000

Page 69

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0003	286A0003				P3 - F/O INSTRUMENT PANEL (continued)										
405CX			OF	ZK	3-11	31-62-22	D03979A	3T			D10081	= A1			YL952-YL999, YN232-YR328
406CO				ZL	0-0	31-62-22	D03977A	= 3T			D10083	= C1			YC051-YD158, YL951-YR328
406CX			OF	ZL	4-11	31-62-22	D03977A	3T			D10083	= A1			YC051-YD158, YN231
406CX			OF	ZL	4-9	31-62-22	D03977A	3T			D10083	= A1			YL951
406CX			OF	ZL	4-6	31-62-22	D03977A	3T			D10083	= A1			YL952-YL999, YN232-YR328
W0008	286A0008				CONTROL STAND (PURCHASED BUNDLE: DWG NO. 254A1221)										
0004	22				3-0	32-64-21	D05148J	5			S00077	3	B		ALL
0005	22				3-0	32-64-21	D05148J	6			S00077	4	B		ALL
0006	22				3-0	33-18-61	D05148J	3			L00382	3	B		ALL
0007	22				3-0	33-18-61	D05148J	1			L00382	1	B		ALL
0008	22				3-0	33-18-61	D05148J	2			L00382	2	B		ALL
0009	20				3-0	33-11-41	TB0800Z	A001	1A		L00400	PWR	B		ALL
0010	20				3-0	33-11-41	TB0800Z	B001	1A		L00400	GND	B		ALL
0011	20				3-0	33-11-41	TB0800Z	A001	1A		L00399	PWR	B		ALL
0012	20				3-0	33-11-41	TB0800Z	B001	1A		L00399	GND	B		ALL
0013	20				3-0	33-11-41	TB0800Z	A001	1A		L00401	PWR	B		ALL
0014	20				3-0	33-11-41	TB0800Z	B001	1A		L00401	GND	B		ALL
0015	20				3-0	33-11-41	TB0800Z	A001	1A		L00462	PWR	B		ALL
0019	20				3-0	31-53-11	D05148J	11			S00651	C	C		ALL
0020	20				3-0	31-53-11	D05148J	10			S00651	NC	C		ALL
0021	20				3-0	31-53-11	D05148J	12			S00651	NO	C		ALL
0039	20				3-0	33-11-41	TB0800Z	B001	1A		L00462	GND	B		ALL
0041	20				3-0	27-62-11	D05148J	8			S00650	C	B		ALL
0042	20				3-0	27-62-11	D05148J	9			S00650	NO	B		ALL
0052	20				3-0	33-11-41	D05148J	7			TB0800Z	B001	1A		ALL
0053	20				3-0	33-11-41	D05148J	4			TB0800Z	A001	1A		ALL
0060	20				3-0	22-13-11	S00149	2	1	*	S00149	4	1	*	ALL
0061	20				3-0	22-13-11	D02485	X2			S00149	1	1		ALL
0062	20				3-0	22-13-11	D02487	6			S00149	4	1	*	ALL
0064	20				3-0	22-13-11	D02487	2			S00149	6	1		ALL
0065	20				3-0	22-13-11	D02487	1			S00149	5	1		ALL
0066	20				3-0	22-13-11	D02487	13			D02485	D3			ALL
0067	20				3-0	22-13-11	D02485	A1		*	D02485	D1			ALL
0068	20				3-0	22-13-11	D02487	12			D02485	A3			ALL
0069	20				3-0	22-13-11	D02487	5			D02485	A1		*	ALL

WIRE LIST

D280A108

91-21-11

Section W0000

Page 70

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0008	286A0008			CONTROL STAND (PURCHASED BUNDLE: DWG NO. 254A1221) (continued)											
0070	20			3-0	22-13-11	D02487		3			D02485	C3			ALL
0071	20			3-0	22-13-11	D02485		B3		*	D02487	9			ALL
0072	20			3-0	22-13-11	D02487		4			D02485	C1			ALL
0073	20			3-0	22-13-11	D02485		B1			S00149	2	1	*	ALL
0074	20			3-0	22-13-11	D02485		B3		*	D02485	X1			ALL
0075	20			3-0	22-13-11	D02487		8			D02485	B2			ALL
0076	20			3-0	22-13-11	D02487		15			D02485	A2			ALL
0077	20			3-0	22-13-11	D02487		14			D02485	D2			ALL
0078	20			3-0	22-13-11	D02487		7			D02485	C2			ALL
0080	20			3-0	27-41-11	D03524		1			S00272	5	1		ALL
0081	20			3-0	27-41-11	D03524		8			S00272	2	1		ALL
0082	20			3-0	27-41-11	D03524		9			S00272	1	1	*	ALL
0084	20			3-0	27-41-11	D03524		7			S00272	3	1		ALL
0085	20			3-0	27-41-11	S00272		1	1	*	S00272	4	1		ALL
0086	20			3-0	27-41-11	D03524		6			S00272	6	1		ALL
0087	20			3-0	27-41-11	S00272		7	1		S00272	10	1	*	ALL
0088	20			3-0	27-41-11	D03524		5			S00272	9	1		ALL
0089	20			3-0	27-41-11	D03524		11			S00272	10	1	*	ALL
0091	20			3-0	27-41-11	D03524		12			S00272	12	1		ALL
0092	20			3-0	27-41-11	D03524		10			S00272	11	1		ALL
0093	20			3-0	27-41-11	D03524		2			S00272	8	1		ALL
A-BL				0-0	27-54-11	S01039		NC			D05150J	8			ALL
A-RD				0-0	27-54-11	S01039		C			D05150J	9			ALL
A-YL				0-0	27-54-11	S01039		NO			D05150J	11			ALL
B-BL				0-0	27-81-51	S01090		NC			D05150J	6			ALL
B-RD				0-0	27-81-51	S01090		C			D05150J	5			ALL
B-YL				0-0	27-81-51	S01090		NO			D05150J	7			ALL

WIRE LIST

D280A108

91-21-11

Section W0000

Page 71 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

	Bundle No.	Part Number			Description		From			To						Effectivity
	Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
I	W0010	286A0010			FWD GALLEY LIGHT MODULE (M01839)											
I	0001	20		PA		1-6	33-26-21	D11400		1		D11396	E			ALL
I	0002	20		PA		1-6	33-26-21	D11400		2		D11396	G			ALL
I	0003	20		PA		1-8	33-26-21	D11400		3		GD00100	ST..	D		ALL
I	0004	22		PA		1-6	33-26-21	D11400		4		D11396	D			ALL
I	0006	22		PA		1-6	33-26-21	D11400		6		D11396	F			ALL
I	0007	20		PA		1-2	33-26-21	D11396		H		GD00100	ST..	D		ALL
I	A-A					0-0	33-26-21	L01300	=A			D11396	J			ALL
I	A-B					0-0	33-26-21	L01300	=B			D11396	K			ALL
I	A-C					0-0	33-26-21	L01300	=C			D11396	C			ALL
I	A-D					0-0	33-26-21	L01300	=D			D11396	B			ALL
I	W0018	286A0018			P18											
I	0001	22		CQ		7-5	21-27-21	C01434	=L	D		D40576J	23			ALL
I	0006	22		CQ		7-5	21-27-31	C01433	=L	D		D40802J	10			ALL
I	0007	24		PK		6-6	21-42-11	C01274	=L	D		D40802J	3			ALL
I	0008	20		CQ		6-4	22-11-11	C01041	=L	D		D41801J	5			ALL
I	0009	20		CQ		7-0	22-11-11	C01045	=L	D		D41803J	1			ALL
I	0010	20		CQ		6-10	22-11-12	C01044	=L	D		D41803J	2			ALL
I	0011	20		CQ		6-11	22-11-12	C01048	=L	D		D41803J	3			ALL
I	0013	14		CQ		9-6	22-13-11	C00849	A1	D		D48901J	1			YC051-YC059
I	0013	14		CQ		10-1	22-13-11	C00849	A1	D		D48901J	1			YC060-YR328
I	0014	14		CQ		9-5	22-13-11	C00849	B1	D		D48901J	2			YC051-YC059
I	0014	14		CQ		10-0	22-13-11	C00849	B1	D		D48901J	2			YC060-YR328
I	0015	14		CQ		9-5	22-13-11	C00849	C1	D		D48901J	3			YC051-YC059
I	0015	14		CQ		9-11	22-13-11	C00849	C1	D		D48901J	3			YC060-YR328
I	0016	20		CQ		7-1	22-14-11	C01049	=L	D		D41807J	3			ALL
I	0017	20		CQ		6-4	22-18-11	C00456	=L	D		D41801J	6			YC051-YC059
I	0017	20		CQ		6-5	22-18-11	C00456	=L	D		D41801J	6			YC060-YR328
I	0018	20		CQ		6-10	22-18-11	C00457	=L	D		D41803J	4			ALL
I	0019	20		PA		6-10	22-23-11	C00286	=L	D		D41803J	7			ALL
I	0020	20		PA		9-9	22-23-11	C01354	=L	D		D40218P	25			YC051-YC059
I	0020	20		PA		9-11	22-23-11	C01354	=L	D		D40218P	25			YC060-YR328
I	0021	20		PA		5-5	22-23-12	C00285	=L	D		D41805J	5			ALL
I	0022	20		PA		6-5	22-23-12	C01429	=L	D		D41807J	24			YC051-YC059
I	0022	20		PA		6-6	22-23-12	C01429	=L	D		D41807J	24			YC060-YL959, YN231-YN235
I	0024	18		CQ		7-1	22-31-11	C00721	=L	D		D41803J	14			YC051-YD155
I	0024	18		CQ		7-1	22-31-31	C00721	=L	D		D41803J	14			YD157-YR328
I	0025	20		CQ		5-3	23-11-11	C00839	A1	D		D41801J	16			YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0010

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From			To			Effectivity		
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W0018	286A0018			P18 (continued)											
0026	20		CQ		5-3	23-11-11	C00839	B1	D		D41801J	17			YC051-YD157
0027	20		CQ		5-4	23-11-11	C00839	C1	D		D41801J	18			YC051-YD157
0029	16		CQ		6-0	23-12-11	C00165	=L	D	*2	D41807J	4			YC051-YC059
0029	16		CQ		6-0	23-12-11	C00165	=L	D	*	D41807J	4			YC060-YD157
0029	16		CQ		6-0	23-12-11	C00165	=L	D		D41807J	4			YD158-YR328
0030	16		CQ		6-0	23-12-11	C00165	=L	D	*2	D41807J	6			YC051-YC059
0030	16		CQ		6-0	23-12-11	C00165	=L	D	*	D41807J	6			YC060-YD157
0033	22		PA		6-0	23-22-11	C00058	=L	D		D40576J	6			ALL
0034	18		PA		9-11	22-31-11	C01141	=L	D		D40218P	39			YC051-YC059
0034	18		PA		10-1	22-31-11	C01141	=L	D		D40218P	39			YC060-YD155
0035	22		PA		11-10	23-42-11	C00073	=L	D		D40538J	7			YC051-YC059
0035	22		PA		11-9	23-42-11	C00073	=L	D		D40538J	7			YC060-YR328
0039	20		PA		7-0	30-71-11	C01473	=L	D		D40802J	11			ALL
0041	20		PA		7-0	30-71-11	C01463	=L	D		D40802J	13			ALL
0045	20		PA		5-4	30-71-11	C00234	=L	D		D40576J	17			ALL
0060	20		PA		10-7	33-25-11	C01407	=L	D		SM00002		9		YD158-YR328
0061	20		PA		10-6	33-25-11	C01408	=L	D		SM00003		9		YD158-YR328
0063	22		CQ		6-8	34-55-11	C00190	=L	D		D41807J	16			YC053-YR328
0066	20		PA		11-2	52-71-13	D40218P		22		D40576J	10			YC051-YC059
0066	20		PA		11-4	52-71-13	D40218P		22		D40576J	10			YC060-YR328
0067	20		PA		12-2	23-15-11	C01420	=L	+		D40218P	8			YC051-YC059
0067	20		PA		12-4	23-15-11	C01420	=L	+		D40218P	8			YC060-YD157
0073	22		PA		6-0	23-15-15	C01422	=L	D		D40576J	21			YC051-YD157
0074	22		PA		4-11	23-71-01	C00107	=L	D	*	D40576J	25			ALL
0075	18		PA		5-1	23-71-01	C01537	=L	D	*	D40576J	24			ALL
0076	22		PA		11-2	23-71-01	C00107	=L	D	*	D40514J	20			YC051-YC059
0076	22		PA		11-5	23-71-01	C00107	=L	D	*	D40514J	20			YC060-YR328
0077	18		PA		11-4	23-71-01	C01537	=L	D	*	D40514J	3	18		YC051-YC059
0077	18		PA		11-8	23-71-01	C01537	=L	D	*	D40514J	3	18		YC060-YR328
0092	20		CQ		11-0	23-32-21	D40218P		12		D41805J	20			YL951-YL967
0092	20		CQ		11-0	23-32-21	D41805J		20		D40218P	12			YN231-YN235
0096	16		CQ		6-10	47-30-11	C01680	=L	D		D40802J	24	16		YD160-YL999, YN232-YR328
0096	16		CQ		6-10	47-30-11	C01680	=L	+		D40802J	24	16		YN231
0106	22		PA		11-2	23-71-01	C01537	=L	+		D40687J	1			YL963-YL999, YN236-YR328
0107	14		CQ		10-10	23-71-01	C01948	=L	+		D40687J	10	14		YL963-YL999, YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W0010

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0018	286A0018			P18 (continued)											
0147	22		CQ		6-0	30-31-11	D15512		B1		D40538J		9		YL968-YL999, YN236-YR328
0148	22		PA		6-0	30-31-11	D15512		A1		D40538J		21		YL968-YL999, YN236-YR328
0151	22		PA		6-0	30-31-11	D15512		C1		D40538J		22		YL968-YL999, YN236-YR328
0152	22		PA		6-0	30-31-11	D15512		D1		D40538J		23		YL968-YL999, YN236-YR328
0153	22		CQ		6-0	30-31-11	D15512		X2		D40538J		24		YL968-YL999, YN236-YR328
0154	22		CQ		7-1	30-31-11	C00523	=L	D	*	D15512		B2		YL968-YL999, YN236-YR328
0155	22		PA		7-1	30-31-11	C00238	=L	D	*	D15512		A2		YL968-YL999, YN236-YR328
0156	22		PA		7-2	30-31-11	C01072	=L	D	*	D15512		C2		YL968-YL999, YN236-YR328
0157	22		PA		7-3	30-31-11	C00236	=L	D	*	D15512		D2		YL968-YL999, YN236-YR328
0158	22		CQ		7-3	30-31-11	C01946	=L	D		D15512		X1		YL968-YL999, YN236-YR328
0162	22		CQ		7-0	30-31-12	C00524	=L	D	*	D15514		A2		YL968-YL999, YN236-YR328
0163	22		CQ		6-10	30-31-12	C01071	=L	D	*	D15514		C2		YL968-YL999, YN236-YR328
0164	22		CQ		6-11	30-31-12	C00525	=L	D	*	D15514		B2		YL968-YL999, YN236-YR328
0165	22		CQ		6-11	30-31-12	C00237	=L	D	*	D15514		D2		YL968-YL999, YN236-YR328
0166	22		CQ		7-3	30-31-12	C01947	=L	D		D15514		X1		YL968-YL999, YN236-YR328
0171	22		CQ		6-1	30-31-12	D15514		A1		D40524J		2		YL968-YL999, YN236-YR328
0172	22		CQ		6-1	30-31-12	D15514		C1		D40524J		3		YL968-YL999, YN236-YR328
0173	22		CQ		6-1	30-31-12	D15514		B1		D40524J		5		YL968-YL999, YN236-YR328
0174	22		CQ		6-1	30-31-12	D15514		D1		D40524J		6		YL968-YL999, YN236-YR328

WIRE LIST
D280A108

91-21-11
Section W0010
Page 3
Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0018	286A0018				P18 (continued)										
0175	22		CQ		6-1	30-31-12	D15514		X2		D40524J	8			YL968-YL999, YN236-YR328
0202	22		PA		12-4	38-21-11	C01096	=L	D		D40220J	2			YC051-YC059
0202	22		PA		12-7	38-21-11	C01096	=L	D		D40220J	2			YC060-YL999, YR301-YR328
0205	22		CQ		12-3	26-16-21	C01522	=L	D		D40504J	2			YC053-YC059
0205	22		CQ		12-8	26-16-21	C01522	=L	D		D40504J	2			YC060-YR328
0206	22		PA		12-2	26-16-21	C01523	=L	D		D40504J	3			YC053-YC059
0206	22		PA		12-8	26-16-21	C01523	=L	D		D40504J	3			YC060-YR328
0207	22		CQ		12-5	26-16-22	C01524	=L	D		D40504J	8			YC053-YC059
0207	22		CQ		12-10	26-16-22	C01524	=L	D		D40504J	8			YC060-YR328
0208	22		CQ		12-4	26-16-22	C01525	=L	D		D40504J	9			YC053-YC059
0208	22		CQ		12-9	26-16-22	C01525	=L	D		D40504J	9			YC060-YR328
0209	22		CQ		12-3	26-23-11	C01526	=L	D		D40504J	11			YC053-YC059
0209	22		CQ		12-8	26-23-11	C01526	=L	D		D40504J	11			YC060-YR328
0210	22		CQ		12-8	26-23-11	C01528	=L	D		D40504J	12			YD158-YD170, YR315-YR316, YR319
0210	22		CQ		12-8	SPARE	C01528	CAP	Y		D40504J	12			YR317
0213	20		CQ		5-3	23-11-11	C00839	A1	D		D41801J	16			YD158-YR328
0214	20		CQ		5-3	23-11-11	C00839	B1	D		D41801J	17			YD158-YR328
0215	20		CQ		5-4	23-11-11	C00839	C1	D		D41801J	18			YD158-YR328
0224	18		CQ		6-10	22-11-11	C01629	=L	+		D41803J	18			YD157-YD170
0224	18		CQ		6-10	22-11-11	C01629	=L	D		D41803J	18			YL951-YR328
0225	20		PA		2-10	21-74-11	D40218P		19		D40208J	1			YD158-YD170
0226	20		PA		2-10	21-74-11	D40218P		20		D40208J	2			YD158-YD170
0227	14		PA		2-10	21-74-11	D40218P		36	14	D40208J	14			YD158-YD170
0228	14		PA		2-10	21-74-11	D40218P		38	14	D40208J	16			YD158-YD170
0229	14		PA		2-10	21-74-11	D40218P		40	14	D40208J	18			YD158-YD170
0260	22		PA		12-0	26-14-11	C01125	=L	D		D40220J	27			YC051-YC059
0260	22		PA		12-3	26-14-11	C01125	=L	D		D40220J	27			YC060-YR328
0300	20		PA		12-3	33-25-11	C01407	=L	D		D40218P	14			YC051-YC059
0300	20		PA		12-5	33-25-11	C01407	=L	D		D40218P	14			YC060-YR328
0301	20		PA		12-3	33-25-11	C01408	=L	D		D40218P	15			YC051-YC059
0301	20		PA		12-4	33-25-11	C01408	=L	D		D40218P	15			YC060-YR328
0302	24		PK		12-0	33-25-11	C00442	=L	D		D40218P	21			YC051-YC059
0302	24		PK		12-2	33-25-11	C00442	=L	D		D40218P	21			YC060-YR328
0303	18		PA		12-2	33-25-11	C01405	=L	D		D40218P	28			YC051-YC059
0303	18		PA		12-4	33-25-11	C01405	=L	D		D40218P	28			YC060-YR328
0304	18		PA		12-1	33-25-11	C01406	=L	D		D40218P	31			YC051-YC059

WIRE LIST

D280A108

91-21-11

Section W0010

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0018	286A0018				P18 (continued)										
0304	18		PA		12-3	33-25-11	C01406	= L	D		D40218P	31			YC060-YR328
0305	18		PA		3-4	33-25-11	D40198J	18			D40218P	29			YC051-YC059
0305	18		PA		3-3	33-25-11	D40198J	18			D40218P	29			YC060-YR328
0306	18		PA		2-4	33-25-11	SM00004		9		D40218P	30			YC051-YC059
0306	18		PA		2-11	33-25-11	SM00004		9		D40218P	30			YC060-YL999, YR301-YR328
0306	18		PA		2-5	33-25-11	SM00004		9		D40218P	30			YN231-YN501
0307	20		PA		2-11	33-25-11	SM00003		9		D40218P	16			YC051-YL999, YR301-YR328
0307	20		PA		2-5	33-25-11	SM00003		9		D40218P	16			YN231-YN501
0308	20		PA		2-4	33-25-11	SM00002		9		D40218P	17			YC051-YC059
0308	20		PA		2-11	33-25-11	SM00002		9		D40218P	17			YC060-YL999, YR301-YR328
0308	20		PA		2-5	33-25-11	SM00002		9		D40218P	17			YN231-YN501
0309	18		PA		2-4	33-25-11	SM00001		9		D40218P	27			YC051-YC059
0309	18		PA		2-11	33-25-11	SM00001		9		D40218P	27			YC060-YL999, YR301-YR328
0309	18		PA		2-5	33-25-11	SM00001		9		D40218P	27			YN231-YN501
0310	18		PA		2-11	33-25-11	SM00001		9		D40198J	19			YC051-YL999, YR301-YR328
0310	18		PA		2-7	33-25-11	SM00001		9		D40198J	19			YN231-YN501
0311	18		PA		2-11	33-25-11	SM00001		9		D40198J	9			YC051-YL999, YR301-YR328
0311	18		PA		2-7	33-25-11	SM00001		9		D40198J	9			YN231-YN501
0312	20		PA		2-11	33-25-11	SM00002		9		D40198J	8			YC051-YL999, YR301-YR328
0312	20		PA		2-7	33-25-11	SM00002		9		D40198J	8			YN231-YN501
0313	20		PA		2-11	33-25-11	SM00002		9		D40198J	7			YC051-YL999, YR301-YR328
0313	20		PA		2-7	33-25-11	SM00002		9		D40198J	7			YN231-YN501
0314	20		PA		2-1	33-25-11	SM00003		9		D40298J	8			YC051-YC059
0314	20		PA		2-6	33-25-11	SM00003		9		D40298J	8			YC060-YD170, YN231-YN501
0314	20		PA		2-4	33-25-11	SM00003		9		D40298J	8			YL951-YL999, YR301-YR328
0315	20		PA		2-1	33-25-11	SM00003		9		D40298J	7			YC051-YC059
0315	20		PA		2-6	33-25-11	SM00003		9		D40298J	7			YC060-YD170, YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W0010

Page 5

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W0018	286A0018				P18 (continued)											
0315	20		PA		2-4	33-25-11		SM00003			9		D40298J	7		YL951-YL999, YR301-YR328
0316	18		PA		2-1	33-25-11		SM00004			9		D40298J	19		YC051-YC059
0316	18		PA		2-6	33-25-11		SM00004			9		D40298J	19		YC060-YD170, YN231-YN501
0316	18		PA		2-4	33-25-11		SM00004			9		D40298J	19		YL951-YL999, YR301-YR328
0317	18		PA		2-1	33-25-11		SM00004			9		D40298J	9		YC051-YC059
0317	18		PA		2-6	33-25-11		SM00004			9		D40298J	9		YC060-YD170, YN231-YN501
0317	18		PA		2-4	33-25-11		SM00004			9		D40298J	9		YL951-YL999, YR301-YR328
0318	22		PA		12-2	33-26-31		C00163	=L	D			D40220J	8		YC051-YC059
0318	22		PA		12-5	33-26-31		C00163	=L	D			D40220J	8		YC060-YN260
0318	20		PA		12-5	33-26-31		C01648	=L	D			D40220J	8		YN501-YR328
0319	20		PA		11-10	33-26-31		C01217	=L	D			D40220J	7		YC051-YC059
0319	20		PA		12-1	33-26-31		C01217	=L	D			D40220J	7		YC060-YL967, YN231-YN235
0319	20		PA		12-2	33-26-31		C01217	=L	D			D40220J	7		YL968-YL999, YN236-YR328
0321	22		PA		11-10	33-27-11		C01404	=L	D			D40298J	11		YC051-YC059
0321	22		PA		12-4	33-27-11		C01404	=L	D			D40298J	11		YC060-YR328
0322	22		PA		2-1	33-27-11		SM00005			9		D40298J	12		YC051-YC059
0322	22		PA		2-6	33-27-11		SM00005			9		D40298J	12		YC060-YD170, YN231-YN501
0322	22		PA		2-11	33-27-11		SM00005			9		D40298J	12		YL951-YL999, YR301-YR328
0323	22		PA		2-11	33-27-11		D40198J			13		D40298J	13		YC051-YL999, YR301-YR328
0323	22		PA		2-0	33-27-11		D40198J			13		D40298J	13		YN231-YN501
0324	22		PA		2-11	33-27-11		D40198J			14		D40298J	14		YC051-YL999, YR301-YR328
0324	22		PA		2-0	33-27-11		D40198J			14		D40298J	14		YN231-YN501
0325	22		PA		10-6	33-27-11		C01403	=L	D			SM00006		9	ALL
0326	22		PA		2-11	33-27-11		SM00005			9		D40198J	12		YC051-YL999, YR301-YR328
0326	22		PA		2-7	33-27-11		SM00005			9		D40198J	12		YN231-YN501
0327	22		PA		2-11	33-27-11		SM00006			9		D40198J	11		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W0010

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0018	286A0018				P18 (continued)										
0327	22		PA		2-7	33-27-11	SM00006			9	D40198J	11			YN231-YN501
0328	22		PA		2-3	33-27-11	SM00006			9	D40220J	29			YC051-YC059
0328	22		PA		2-11	33-27-11	SM00006			9	D40220J	29			YC060-YL999, YR301-YR328
0328	22		PA		2-6	33-27-11	SM00006			9	D40220J	29			YN231-YN501
0329	22		PA		2-3	33-27-11	SM00005			9	D40220J	28			YC051-YC059
0329	22		PA		2-11	33-27-11	SM00005			9	D40220J	28			YC060-YL999, YR301-YR328
0329	22		PA		2-6	33-27-11	SM00005			9	D40220J	28			YN231-YN501
0330	22		PA		9-8	33-27-11	SM00005			9	D41807J	14			ALL
0331	18		PA		12-3	33-41-11	C00110	=L	D		D40522J	10			YC051-YC059
0331	18		PA		12-4	33-41-11	C00110	=L	D		D40522J	10			YC060-YR328
0332	20		CQ		12-1	33-42-11	C00274	=L	D		D40504J	1			YC051-YC059
0332	20		CQ		12-6	33-42-11	C00274	=L	D		D40504J	1			YC060-YR328
0333	20		PA		12-1	33-42-11	C00273	=L	D		D40538J	10			YC051-YC059
0333	20		PA		12-0	33-42-11	C00273	=L	D		D40538J	10			YC060-YR328
0334	20		CQ		11-11	33-42-11	C00272	=L	D		D40524J	1			YC051-YC059
0334	20		CQ		12-2	33-42-11	C00272	=L	D		D40524J	1			YC060-YR328
0335	20		CQ		12-1	33-42-11	C00271	=L	D		D40522J	9			YC051-YC059
0335	20		CQ		12-2	33-42-11	C00271	=L	D		D40522J	9			YC060-YL999, YR301-YR328
0335	20		PA		12-2	33-42-11	C00271	=L	D		D40522J	9			YN231-YN501
0336	20		PA		12-1	33-43-11	C00113	=L	D		D40538J	3			YC051-YC059
0336	20		PA		12-0	33-43-11	C00113	=L	D		D40538J	3			YC060-YR328
0337	20		PA		12-1	33-43-11	C00114	=L	D		D40514J	10			YC051-YC059
0337	20		PA		12-4	33-43-11	C00114	=L	D		D40514J	10			YC060-YR328
0338	20		PA		11-11	33-44-11	C00111	=L	D		D40504J	6			YC051-YC059
0338	20		PA		12-4	33-44-11	C00111	=L	D		D40504J	6			YC060-YR328
0339	20		PA		12-0	33-44-12	C00115	=L	D		D40504J	5			YC051-YC059
0339	20		PA		12-5	33-44-12	C00115	=L	D		D40504J	5			YC060-YR328
0340	18		PA		11-9	33-45-11	C00245	=L	D		D40524J	4			YC051-YC059
0340	18		PA		12-0	33-45-11	C00245	=L	D		D40524J	4			YC060-YR328
0341	18		PA		11-9	33-45-11	C00123	=L	D		D40504J	10			YC051-YC059
0341	18		PA		12-3	33-45-11	C00123	=L	D		D40504J	10			YC060-YD170
0342	18		PA		12-0	33-45-11	C00244	=L	D		D40504J	4			YC051-YC059
0342	18		PA		12-5	33-45-11	C00244	=L	D		D40504J	4			YC060-YR328
0343	20		PA		12-2	33-49-11	C00644	=L	D		D40514J	11			YC051-YC059
0343	20		PA		12-6	33-49-11	C00644	=L	D		D40514J	11			YC060-YR328
0344	20		PA		12-0	33-51-11	C00250	=L	D		D40522J	1			YC051-YC059

WIRE LIST

D280A108

91-21-11

Section W0010

Page 7

Nov 12/2012

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0018	286A0018			P18 (continued)											
0344	20		PA		12-1	33-51-11	C00250	=L	D		D40522J	1			YC060-YR328
0345	20		PA		11-11	33-51-11	C01357	=L	D		D40522J	5			YC051-YC059
0345	20		PA		12-0	33-51-11	C01357	=L	D		D40522J	5			YC060-YR328
0346	20		PA		11-9	33-51-11	C01358	=L	D		D40522J	6			YC051-YC059
0346	20		PA		11-10	33-51-11	C01358	=L	D		D40522J	6			YC060-YR328
0350	22		CQ		6-4	35-11-11	C00156	=L	D	*	D40802J	8			ALL
0351	16		CQ		6-7	35-21-11	C00783	=L	D		D40830J	8			ALL
0352	16		CQ		6-6	35-21-11	C00784	=L	D		D40830J	7			ALL
0353	22		CQ		6-5	35-21-11	C00785	=L	D		D40830J	6			ALL
0354	22		CQ		6-4	35-21-11	C00156	=L	D	*	D40802J	1			ALL
0355	16		CQ		2-1	35-21-11	SM00007		9		D40298J	15			YC051-YC059
0355	16		CQ		2-6	35-21-11	SM00007		9		D40298J	15			YC060-YR328
0356	16		CQ		2-1	35-21-11	SM00007		9		D40298J	16			YC051-YC059
0356	16		CQ		2-6	35-21-11	SM00007		9		D40298J	16			YC060-YR328
0357	16		CQ		2-3	35-21-11	SM00008		9		D40198J	15			YC051-YC059
0357	16		CQ		2-11	35-21-11	SM00008		9		D40198J	15			YC060-YL999, YR301-YR328
0357	16		CQ		2-7	35-21-11	SM00008		9		D40198J	15			YN231-YN501
0358	16		CQ		2-3	35-21-11	SM00008		9		D40198J	16			YC051-YC059
0358	16		CQ		2-11	35-21-11	SM00008		9		D40198J	16			YC060-YL999, YR301-YR328
0358	16		CQ		2-7	35-21-11	SM00008		9		D40198J	16			YN231-YN501
0359	16		CQ		9-6	35-21-11	SM00007		9		D40830J	9			ALL
0360	16		CQ		9-6	35-21-11	SM00008		9		D40830J	10			ALL
0361	22		PA		12-2	38-21-11	C00104	=L	D		D40220J	3			YC051-YC059
0361	22		PA		12-6	38-21-11	C00104	=L	D		D40220J	3			YC060-YR328
0362	22		PA		12-3	38-21-11	C01073	=L	D		D40220J	4			YC051-YC059
0362	22		PA		12-6	38-21-11	C01073	=L	D		D40220J	4			YC060-YR328
0378	20		PA		12-6	38-32-13	C01423	=L	D		D40220J	20			YC051-YC059
0378	20		PA		12-10	38-32-13	C01423	=L	D		D40220J	20			YC060-YR328
0379	24		PK		10-9	33-25-11	D40538J		2		D40802J	2			YC051-YC059
0379	24		PK		10-8	33-25-11	D40538J		2		D40802J	2			YC060-YR328
0382	18		PA		6-9	33-45-11	C00123	=L	D		D40830J	12			YL951-YR328
0388	18		PA		12-1	33-45-11	C01518	=L	D		D40504J	10			YL951-YR328
0390	20		CQ		12-4	31-32-15	C01192	=L	D	*	D40218P	4			YL951-YR328
0394	20		CQ		6-3	34-61-11	C01017	=L	D		D41809J	6			YC053-YR328
0414	16		PA		7-0	47-30-11	C01657	=L	D		D40830J	13			YD160-YL999, YN232-YR328
0414	16		PA		7-0	47-30-11	C01657	=L	+		D40830J	13			YN231

WIRE LIST

D280A108

91-21-11

Section W0010

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0018	286A0018			P18 (continued)											
0502	22		CQ		10-10	23-27-11	D41805J	26			D40218P	7			YC051-YC059
0502	22		CQ		11-0	23-27-11	D41805J	26			D40218P	7			YC060-YD157
0504	22		CQ		10-10	23-27-13	D40218P	6			D41805J	25			YC051-YC059
0504	22		CQ		11-0	23-27-13	D40218P	6			D41805J	25			YC060-YD157
0505	16		CQ		12-1	23-12-31	C00471	=L	D		D40218P	34			YC051-YC059
0505	16		CQ		12-3	23-12-31	C00471	=L	D	*	D40218P	34			YC060-YD157
0505	16		CQ		12-3	23-12-31	C00471	=L	D		D40218P	34			YD158-YR328
0506	16		CQ		12-1	23-12-31	C00471	=L	D		D40218P	35			YC051-YC059
0506	16		CQ		12-3	23-12-31	C00471	=L	D	*	D40218P	35			YC060-YD157
0507	18		PA		7-0	38-31-31	C01462	=L	D		D40576J	14			YL951-YR328
0508	14		PA		6-1	21-25-11	C00911	A1	D		D40576J	22			YC051-YL999, YR301-YR328
0509	14		PA		6-2	21-25-11	C00911	B1	D		D40576J	18			YC051-YL999, YR301-YR328
0510	14		PA		6-3	21-25-11	C00911	C1	D		D40576J	20			YC051-YL999, YR301-YR328
0511	22		PA		6-3	21-25-11	C01156	=L	D		D40576J	15			YC051-YL999, YR301-YR328
0512	20		PA		6-4	23-29-11	C01143	=L	+		D41809J	13			YC051-YD157
0513	16		CQ		12-8	25-29-11	C01460	=L	D		D40220J	21			YC053-YC059
0513	16		CQ		12-11	25-29-11	C01460	=L	D		D40220J	21			YC060-YD170
0514	20		CQ		5-0	34-61-11	C01238	=L	D		D41805J	2			YC051-YC052
0514	20		CQ		6-4	34-61-11	C01238	=L	D		D41809J	7			YC053-YR328
0515	20		CQ		6-1	34-61-22	C01192	=L	D		D41803J	11			YC051-YD170
0515	20		CQ		6-1	34-61-22	C01192	=L	D	*	D41803J	11			YL951-YR328
0517	20		PA		10-10	34-21-15	C00412	=L	D		D40514J	1			YC051-YC059
0517	20		PA		11-1	34-21-15	C00412	=L	D		D40514J	1			YC060-YR328
0520	22		CQ		11-0	23-27-31	D40218P	2			D41805J	22			YD158-YR328
0701	22		CQ		5-3	27-32-11	C01205	=L	D		D41809J	8			ALL
0702	22		CQ		5-2	27-32-11	C01204	=L	D		D41809J	9			ALL
0703	22		CQ		5-2	27-32-11	C01392	=L	D		D41809J	10			ALL
0704	22		PA		5-2	27-32-11	C01208	=L	D		D41803J	5			ALL
0706	10		CQ		6-1	30-42-11	C00055	=L	D		D41809J	27	10		YC062-YR328
0707	10		CQ		5-11	30-42-11	C00054	=L	D		D41803J	24	10		YC062-YR328
0710	22		PA		11-5	30-11-11	C00146	=L	D		D40514J	22			YC051-YC059
0710	22		PA		11-8	30-11-11	C00146	=L	D		D40514J	22			YC060-YR328
0711	22		PA		11-7	30-21-11	C01001	=L	D		D40514J	9			YC051-YC059
0711	22		PA		11-11	30-21-11	C01001	=L	D		D40514J	9			YC060-YR328
0712	22		PA		11-6	30-21-11	C00148	=L	D		D40514J	23			YC051-YC059

WIRE LIST

D280A108

91-21-11

Section W0010

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W0018	286A0018				P18 (continued)											
0712	22		PA		11-10	30-21-11		C00148	=L	D		D40514J	23			YC060-YR328
0713	22		PA		11-6	30-21-21		C01002	=L	D		D40538J	6			YC051-YC059
0713	22		PA		11-5	30-21-21		C01002	=L	D		D40538J	6			YC060-YR328
0714	22		PA		11-5	30-21-21		C00149	=L	D		D40538J	1			YC051-YC059
0714	22		PA		11-4	30-21-21		C00149	=L	D		D40538J	1			YC060-YR328
0715	22		PA		11-4	30-31-11		C00236	=L	D		D40522J	8			YC051-YC059
0715	22		PA		11-5	30-31-11		C00236	=L	D		D40522J	8			YC060-YL967, YN231-YN235
0715	22		PA		11-5	30-31-11		C00236	=L	D	*	D40522J	8			YL968-YL999, YN236-YR328
0716	22		PA		11-2	30-31-11		C00238	=L	D		D40522J	12			YC051-YC059
0716	22		PA		11-3	30-31-11		C00238	=L	D		D40522J	12			YC060-YL967, YN231-YN235
0716	22		PA		11-3	30-31-11		C00238	=L	D	*	D40522J	12			YL968-YL999, YN236-YR328
0717	22		CQ		11-2	30-31-11		C00523	=L	D		D40522J	3			YC051-YC059
0717	22		CQ		11-3	30-31-11		C00523	=L	D		D40522J	3			YC060-YL967, YN231-YN235
0717	22		CQ		11-3	30-31-11		C00523	=L	D	*	D40522J	3			YL968-YL999, YN236-YR328
0718	22		PA		11-3	30-31-11		C01072	=L	D		D40522J	11			YC051-YC059
0718	22		PA		11-4	30-31-11		C01072	=L	D		D40522J	11			YC060-YL967, YN231-YN235
0718	22		PA		11-4	30-31-11		C01072	=L	D	*	D40522J	11			YL968-YL999, YN236-YR328
0719	22		CQ		10-11	30-31-12		C00237	=L	D		D40514J	14			YC051-YC059
0719	22		CQ		11-3	30-31-12		C00237	=L	D		D40514J	14			YC060-YL967, YN231-YN235
0719	22		CQ		11-3	30-31-12		C00237	=L	D	*	D40514J	14			YL968-YL999, YN236-YR328
0720	22		CQ		11-1	30-31-12		C00524	=L	D		D40514J	24			YC051-YC059
0720	22		CQ		11-4	30-31-12		C00524	=L	D		D40514J	24			YC060-YL967, YN231-YN235
0720	22		CQ		11-4	30-31-12		C00524	=L	D	*	D40514J	24			YL968-YL999, YN236-YR328
0721	22		CQ		11-0	30-31-12		C00525	=L	D		D40514J	13			YC051-YC059
0721	22		CQ		11-3	30-31-12		C00525	=L	D		D40514J	13			YC060-YL967, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W0010

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0018	286A0018				P18 (continued)										
0721	22		CQ		11-3	30-31-12	C00525	=L	D	*	D40514J	13			YL968-YL999, YN236-YR328
0722	22		CQ		10-10	30-31-12	C01071	=L	D		D40514J	12			YC051-YC059
0722	22		CQ		11-2	30-31-12	C01071	=L	D		D40514J	12			YC060-YL967, YN231-YN235
0722	22		CQ		11-2	30-31-12	C01071	=L	D	*	D40514J	12			YL968-YL999, YN236-YR328
0723	24		B6		10-10	30-41-11	C00224	=L	D		D40514J	15			YC051-YC059
0723	24		B6		11-1	30-41-11	C00224	=L	D		D40514J	15			YC060-YR328
0724	24		B6		10-10	30-41-11	C00227	=L	D		D40514J	16			YC051-YC059
0724	24		B6		11-1	30-41-11	C00227	=L	D		D40514J	16			YC060-YR328
0725	24		PK		10-10	30-41-12	C00226	=L	D		D40538J	11			YC051-YC059
0725	24		PK		10-9	30-41-12	C00226	=L	D		D40538J	11			YC060-YR328
0726	24		PK		10-11	30-41-12	C00225	=L	D		D40538J	12			YC051-YC059
0726	24		PK		10-10	30-41-12	C00225	=L	D		D40538J	12			YC060-YR328
0727	18		CQ		11-3	30-42-11	C00054	=L	D		D40504J	7			YC051-YC059
0727	18		CQ		11-8	30-42-11	C00054	=L	D		D40504J	7			YC060-YR328
0728	18		PA		11-1	30-42-11	C00055	=L	D		D40524J	10			YC051-YC059
0728	18		PA		11-4	30-42-11	C00055	=L	D		D40524J	10			YC060-YR328
0731	20		PA		6-1	30-71-11	C00233	=L	D		D40802J	12			ALL
0733	20		PA		5-5	30-71-11	C00700	=L	D		D40576J	19			ALL
0741	22		PA		4-11	31-31-11	C00109	=L	D	*1	D41805J	7			ALL
0742	22		PA		11-6	31-31-11	C00109	=L	D	*1	D40514J	21			YC051-YC059
0742	22		PA		11-10	31-31-11	C00109	=L	D	*1	D40514J	21			YC060-YR328
0743	22		PA		11-7	31-31-11	C00468	=L	D	*	D40514J	17			YC051-YC059
0743	22		PA		11-11	31-31-11	C00468	=L	D	*	D40514J	17			YC060-YR328
0744	22		PA		5-4	31-31-11	C00468	=L	D	*	D40576J	1			ALL
0749	22		PA		4-11	31-31-14	C00544	=L	D		D41805J	6			ALL
0801	22		CQ		4-9	34-16-11	C00170	=L	D		D40830J	14			ALL
0802	20		CQ		5-5	34-21-11	C00357	=L	D		D41807J	27			YC051-YD157
0803	20		CQ		5-5	34-21-11	C00425	=L	D		D41809J	4			ALL
0804	20		CQ		7-0	34-21-11	C01007	=L	D		D41809J	5			ALL
0805	16		CQ		6-10	34-21-11	C01009	=L	D		D41803J	22			ALL
0807	22		CQ		6-8	34-31-11	C01479	=L	D		D41807J	7			ALL
0808	16		CQ		4-11	31-62-11	C01363	=L	D		D41807J	8			ALL
0809	16		CQ		4-11	31-62-11	C01365	=L	D		D41807J	2			YC053-YR328
0810	16		CQ		4-10	31-62-11	C01372	=L	D		D41807J	10			ALL
0811	22		CQ		6-5	34-22-11	C01386	=L	D		D41807J	23			YC051-YD158
0811	22		CQ		6-6	34-22-11	C01386	=L	D		D41807J	23			YD160-YR328

WIRE LIST

D280A108

91-21-11

Section W0010

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0018						P18 (continued)									
	0812	22		CQ	6-7	34-51-11	C01378	=L	D		D41807J	19			ALL
	0813	22		CQ	6-0	34-33-11	C01384	=L	D		D41805J	4			ALL
	0814	22		CQ	6-10	34-51-41	C01376	=L	D		D41807J	15			ALL
	0815	20		CQ	6-7	34-53-11	C00186	=L	D		D41807J	11			YL951-YR328
	0816	22		CQ	12-0	34-24-15	C01551	=L	D		D40218P	11			YD158
	0816	20		CQ	12-0	34-24-15	C01551	=L	D		D40218P	11			YD160-YR328
	0821	20		PA	6-3	34-45-11	C01195	=L	D		D41801J	4			YC051-YC059
	0821	20		PA	6-4	34-45-11	C01195	=L	D		D41801J	4			YC060-YR328
	0822	22		PA	6-2	34-49-11	C01519	=L	D		D40576J	9			YC053-YR328
	0823	22		PA	6-4	34-49-11	C00629	=L	D		D41801J	7			ALL
	0828	20		CQ	6-6	34-53-11	C00186	=L	D		D41807J	11			YC051-YC059
	0828	20		CQ	6-7	34-53-11	C00186	=L	D		D41807J	11			YC060-YD170
	0830	22		CQ	6-6	34-55-11	C00190	=L	D		D41801J	9			YC051-YC052
	0832	22		PA	6-8	34-57-11	C01382	=L	D		D41809J	3			YC051-YL999, YR301-YR328
	0832	22		CQ	6-8	34-57-11	C01382	=L	D		D41809J	3			YN231-YN501
	0836	20		CQ	5-0	34-61-11	C01017	=L	D		D41805J	1			YC051-YC052
	0838	20		CQ	11-9	34-61-18	C00923	=L	D		D40514J	2			YC051-YC058
	0838	20		CQ	11-9	31-32-15	C00923	=L	D		D40514J	2			YC059
	0838	20		CQ	12-1	31-32-15	C00923	=L	D		D40514J	2			YC060-YR328
	0850	20		CQ	5-2	73-22-11	C01314	=L	D		D40576J	11			ALL
	0851	20		CQ	5-2	73-22-11	C01390	=L	D		D40802J	14			ALL
	0852	24		PK	4-10	73-22-31	C01312	=L	D		D40576J	12			ALL
	0853	20		CQ	5-0	74-11-11	C00153	=L	D		D40576J	7			ALL
	0854	20		PA	5-1	74-11-11	C00458	=L	D		D40802J	6			ALL
	0855	24		B6	4-9	76-21-11	C01316	=L	D		D40576J	13			ALL
	0856	24		B6	4-9	76-21-11	C01317	=L	D		D40802J	7			ALL
	0859	18		PA	5-2	78-32-51	C01266	=L	D		D40802J	5	18		ALL
	0860	20		PA	5-0	78-34-11	C00276	=L	D		D40802J	4			ALL
	0861	20		PA	5-1	78-35-11	C01412	=L	D		D40802J	9			ALL
	0862	20		PA	4-7	78-36-11	C01003	=L	D		D41805J	12			ALL
	0863	20		CQ	11-5	80-11-11	C01103	=L	D		D40514J	8			YC051-YC059
	0863	20		CQ	11-9	80-11-11	C01103	=L	D		D40514J	8			YC060-YR328
	0873	22		CQ	5-4	34-24-11	C01387	=L	D		D41807J	9			YC051-YD157
	0880	22		CQ	6-9	34-51-11	C01374	=L	D		D41807J	5			ALL
	0884	22		CQ	4-10	31-62-11	C01369	=L	D		D41807J	17			ALL
	0885	16		CQ	4-11	31-62-11	C01365	=L	D		D41803J	16			YC051-YC052
	0887	16		CQ	5-3	31-62-11	C01359	=L	D		D41809J	15			ALL
	0894	22		PA	4-8	27-32-11	C01208	=B	D		GD01850	DC..	E		ALL

WIRE LIST

D280A108

91-21-11

Section W0010

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W0018	286A0018				P18 (continued)										
2001B	20	PB	GA		3-2	23-70-11	D40218P	43			D40220J	26			YL951-YR328
2001R	20	PB	GA		0-0	23-70-11	D40218P	42			D40220J	25			YL951-YR328
5501	20	PA			6-6	33-17-11	D40218P	9			TB5180A	1	E		YC051-YC059
5501	20	PA			6-8	33-17-11	D40218P	9			TB5180A	1	E		YC060-YR328

WIRE LIST
D280A108

91-21-11
Section W0010
Page 13 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0020	286A0020			P18-BUS WIRING											
0889	06		CQ		1-10	24-53-11	T00038		G	E	GD00154	AC..	E		YC051-YC058
0889	06		CQ		1-11	24-53-11	T00038		G	E	GD00154	AC..	E		YC059-YR328
0891	18		CQ		5-2	24-53-11	C02046		=L	D	T00038	HV	E		YC051-YD158
0891	18		CQ		5-0	24-53-11	C02046		=L	D	T00038	HV	E		YD160-YL959, YN231-YN235
0891	18		CQ		5-1	24-53-11	C02046		=L	D	T00038	HV	E		YL963-YL999, YN236-YR328
0892	08		CQ		4-2	24-53-11	T00038		LV	E	TB5180B	7	E		ALL
6001	12		CQ		4-8	24-51-11	C00629		=B	D	TB5180E	1	E		YC051-YC058
6001	12		CQ		4-8	24-51-11	TB5180E		1	E	C00629	=B	D		YC059, YD151-YD158
6001	12		CQ		4-3	24-51-13	TB5180E		1	E	C00629	=B	D		YC060-YC070
6001	12		CQ		4-8	24-51-13	TB5180E		1	E	C00629	=B	D		YD160-YR328
6002	16		CQ		4-7	24-51-11	C01195		=B	D	TB5180E	3	E		YC051-YC058
6002	12		CQ		4-7	24-51-11	TB5180E		3	E	C01195	=B	D		YC059, YD151-YD158
6002	12		CQ		4-7	24-51-13	TB5180E		3	E	C01195	=B	D		YC060-YC070, YD160-YR328
6003	16		CQ		4-8	24-51-11	C01429		=B	D	TB5180E	5	E		YC051-YC058
6003	14		CQ		4-8	24-51-11	TB5180E		5	E	C01429	=B	D		YC059, YD151-YD158
6003	14		CQ		4-11	24-51-13	TB5180E		5	E	C01429	=B	D		YC060-YC070
6003	14		CQ		4-8	24-51-13	TB5180E		5	E	C01429	=B	D		YD160-YL959, YN231-YN235
6007	16		CQ		4-4	24-51-11	TB5180E		2	E	C00227	=B	D		YC051-YC059, YD151-YD158
6007	16		CQ		3-10	24-51-11	TB5180E		2	E	C00227	=B	D		YC060-YC070
6007	16		CQ		4-4	24-51-13	TB5180E		2	E	C00227	=B	D		YD160-YL959, YN231-YN235
6007	16		CQ		4-5	24-51-13	TB5180E		2	E	C00227	=B	D		YL963-YL999, YN236-YR328
6008	14		CQ		4-4	24-51-11	C00238		=B	D	TB5180E	4	E		YC051-YC059
6008	14		CQ		4-4	24-51-13	TB5180E		4	E	C00238	=B	D	*	YC060-YC070, YD160-YL959
6008	14		CQ		4-4	24-51-11	TB5180E		4	E	C00238	=B	D	*	YD151-YD158
6008	14		CQ		4-5	24-51-13	TB5180E		4	E	C00238	=B	D	*	YL963-YL999, YR301-YR328
6008	14		CQ		4-4	24-51-13	C00238		=B	D	TB5180E	4	E		YN231-YN235
6008	14		CQ		4-5	24-51-13	C00238		=B	D	TB5180E	4	E		YN236-YN501
6009	10		CQ		4-2	24-51-11	C02046		=B	D	TB5180E	6	E		YC051-YC059

WIRE LIST

D280A108

91-21-11

Section W0020

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0020	286A0020			P18-BUS WIRING (continued)											
6009	10	CQ		4-2	24-51-13	TB5180E	6	E		C02046	=B	D		YC060-YC070, YD160-YL959, YN231-YN235	
6009	10	CQ		4-2	24-51-11	TB5180E	6	E		C02046	=B	D		YD151-YD158	
6009	10	CQ		4-3	24-51-13	TB5180E	6	E		C02046	=B	D		YL963-YL999, YN236-YR328	
6012	16	CQ		1-11	24-51-11	C00238	=B	D	*	C00111	=B	D		YC051-YC059, YD151-YD158	
6012	16	CQ		1-11	24-51-13	C00238	=B	D	*	C00111	=B	D		YC060-YC070, YD160-YL959, YN231-YN235	
6012	16	CQ		2-0	24-51-13	C00238	=B	D	*	C00111	=B	D		YL963-YL999, YN236-YR328	
6014	12	CQ		2-2	24-51-11	C00236	=B	D		C00115	=B	D		YC051-YC059, YD151-YD158	
6014	12	CQ		2-2	24-51-13	C00236	=B	D		C00115	=B	D		YC060-YC070, YD160-YR328	
6015	16	CQ		1-10	24-51-11	C00271	=B	D		C00146	=B	D		YC051-YC059, YD151-YD158	
6015	16	CQ		1-10	24-51-13	C00271	=B	D		C00146	=B	D		YC060-YC070, YD160-YR328	
6016	16	CQ		5-4	24-51-12	TB5180E	7	E		C00644	=B	D		YN231-YN501	
6017	14	CQ		4-1	24-51-12	TB5180E	8	E		C00700	=B	D		YN231-YN501	
6018	14	CQ		4-8	24-51-12	TB5180E	9	E		C00104	=B	D		YN231-YN501	
6019	16	PA		4-4	24-51-21	C00107	=B	D		TB5180D	3	E		YC051-YC059	
6019	16	PA		4-6	24-51-23	TB5180D	3	E		C00107	=B	D		YC060-YC070	
6019	16	PA		4-6	24-51-21	TB5180D	3	E		C00107	=B	D		YD151-YD157	
6019	16	HA		4-6	24-51-21	TB5180D	3	E		C00107	=B	D		YD158	
6019	16	HA		4-6	24-51-23	TB5180D	3	E		C00107	=B	D		YD160-YR328	
6020	14	PA		4-10	24-61-23	TB5180D	1	E		C00471	=B	D	*	YC051-YC059	
6020	14	PA		5-0	24-61-23	TB5180D	1	E		C00471	=B	D	*	YC060-YD157	
6020	16	HA		5-0	24-61-23	TB5180D	1	E		C00471	=B	D	*	YD158-YL963, YN231-YN235	
6020	12	HA		5-0	24-61-23	TB5180D	1	E		C00471	=B	D	*	YL964-YL999, YN236-YN501	
6020	12	HA		5-0	24-61-23	TB5180D	1	E		C00471	=B	D		YR301-YR328	
6021	12	PA		4-2	24-51-21	C01071	=B	D		TB5180D	2	E		YC051-YC059	
6021	12	PA		4-4	24-51-21	TB5180D	2	E		C01071	=B	D		YC060-YD157	
6021	12	HA		4-4	24-51-21	TB5180D	2	E		C01071	=B	D		YD158	

WIRE LIST

D280A108

91-21-11

Section W0020

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description		From				To				Effectivity		
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type		Splice	
W0020	286A0020			P18-BUS WIRING (continued)												
6021	12		HA		4-4	24-51-23	TB5180D	2	E		C01071	=B	D		YD160-YR328	
6022	16		PA		4-4	24-51-21	TB5180D	3	E		C00524	=B	D	*	YC051-YC059	
6022	16		PA		4-6	24-51-21	TB5180D	3	E		C00524	=B	D	*	YC060-YD157	
6022	16		HA		4-6	24-51-21	TB5180D	3	E		C00524	=B	D		YD158	
6022	16		HA		4-6	24-51-23	TB5180D	3	E		C00524	=B	D	*	YD160-YR328	
6023	16		PA		4-2	24-51-21	C00525	=B	D		TB5180D	4	E		YC051-YC059	
6023	16		PA		4-4	24-51-23	TB5180D	4	E		C00525	=B	D		YC060-YC070	
6023	16		PA		4-4	24-51-21	TB5180D	4	E		C00525	=B	D		YD151-YD157	
6023	16		HA		4-4	24-51-21	TB5180D	4	E		C00525	=B	D		YD158	
6023	16		HA		4-4	24-51-23	TB5180D	4	E		C00525	=B	D		YD160-YR328	
6024	16		PA		1-11	24-51-21	C00273	=B	D		C00225	=B	D		YC051-YD157	
6024	16		HA		1-11	24-51-21	C00273	=B	D		C00225	=B	D		YD158	
6024	16		HA		1-11	24-51-23	C00273	=B	D		C00225	=B	D		YD160-YR328	
6025	16		PA		1-6	24-51-21	C00272	=B	D		C00524	=B	D	*	YC051-YD157	
6025	16		HA		1-6	24-51-21	C00272	=B	D		C00524	=B	D	*	YD158	
6025	16		HA		1-6	24-51-23	C00272	=B	D		C00524	=B	D	*	YD160-YR328	
6027	14		CQ		3-7	24-53-11	C00285	=B	D		TB5180B	8	E		YC051-YC058	
6027	14		CQ		3-9	24-53-11	C00285	=B	D		TB5180B	8	E		YC059, YN231-YN235	
6027	14		CQ		3-9	24-53-11	TB5180B	8	E		C00285	=B	D		YC060-YL963	
6027	14		CQ		3-10	24-53-11	TB5180B	8	E		C00285	=B	D		YL964-YL999, YR301-YR328	
6027	14		CQ		3-10	24-53-11	C00285	=B	D		TB5180B	8	E		YN236-YN501	
6028	14		CQ		6-4	24-53-11	C00544	=B	D		TB5180B	7	E		YC051-YC059, YN231-YN501	
6028	14		CQ		6-4	24-53-11	TB5180B	7	E		C00544	=B	D		YC060-YL999, YR301-YR328	
6029	08		CQ		1-6	24-53-11	C01217	=B	D	*	C00234	=B	D		YC051-YD157	
6029	14		CQ		1-9	24-53-11	C01217	=B	D	*	C00234	=B	D		YD158-YL967	
6029	14		CQ		1-10	24-53-11	C01217	=B	D	*	C00234	=B	D		YL968-YL999, YR301-YR328	
6029	14		CQ		1-9	24-53-11	C00234	=B	D		C01217	=B	D	*	YN231-YN235	
6029	14		CQ		1-10	24-53-11	C00234	=B	D		C01217	=B	D	*	YN236-YN501	
6031	08		CQ		1-0	24-53-11	C01217	=B	D	*	C00123	=B	D		YC051-YC053	
6031	10		CQ		1-0	24-53-11	C01217	=B	D	*	C00123	=B	D		YC054-YD170	
6031	10		CQ		1-0	24-53-11	C01217	=B	D	*	C00123	=B	D	*	YL951-YL967, YN231-YN235	
6031	10		CQ		0-11	24-53-11	C01217	=B	D	*	C00123	=B	D	*	YL968-YL999, YN236-YR328	
6032	16		GA		6-7	24-53-11	C00245	=B	D		TB5180B	4	E		YC051-YC053	

WIRE LIST

D280A108

91-21-11

Section W0020

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0020	286A0020			P18-BUS WIRING (continued)											
6032	12	PA		6-7	24-53-11	C00245	=B	D		TB5180B	4	E		YC054-YC058	
6032	12	PA		6-8	24-53-11	C00245	=B	D		TB5180B	4	E		YC059	
6032	12	PA		6-8	24-53-11	TB5180B		4	E	C00245	=B	D		YC060-YD157	
6032	12	HA		6-8	24-53-11	TB5180B		4	E	C00245	=B	D		YD158-YL999, YR301-YR328	
6032	12	HA		6-8	24-53-11	C00245	=B	D		TB5180B	4	E		YN231-YN501	
6033	18	CQ		6-2	24-53-11	C01205	=B	D		TB5180B	6	E		YC051-YC059	
6033	18	CQ		6-2	24-53-11	TB5180B		6	E	C01205	=B	D		YC060-YD170	
6033	18	CQ		6-2	24-53-11	TB5180B		6	E	C01205	=B	D	*	YL951-YR328	
6034	14	CQ		3-9	24-54-11	C01007	=B	D		TB5180B	3	E		YC051-YC059	
6034	14	CQ		3-9	24-54-11	TB5180B		3	E	C01007	=B	D		YC060-YD155	
6034	14	CQ		3-2	24-54-11	TB5180F		2	E	C01007	=B	D	*	YD157-YL963, YN231-YN235	
6034	14	CQ		3-3	24-54-11	TB5180F		2	E	C01007	=B	D	*	YL964-YL999, YN236-YR328	
6035	18	CQ		6-0	24-54-11	C00458	=B	D		TB5180B	3	E		YC051-YC052	
6035	18	CQ		6-0	24-54-11	C00458	=B	D	*	TB5180B	3	E		YC053-YC059	
6035	18	CQ		6-0	24-54-11	TB5180B		3	E	C00458	=B	D		YC060-YD155	
6035	18	CQ		5-0	24-54-11	TB5180F		2	E	C00458	=B	D	*	YD157-YL963, YN231-YN235	
6035	18	CQ		5-1	24-54-11	TB5180F		2	E	C00458	=B	D	*	YL964-YL999, YN236-YR328	
6036	14	CQ		1-6	24-54-11	C01386	=B	D		C01007	=B	D		YC051-YC059	
6036	14	CQ		1-6	24-54-11	C01007	=B	D		C01386	=B	D		YC060-YD155	
6036	14	CQ		1-6	24-54-11	C01007	=B	D	*	C01386	=B	D		YD157-YL963, YN231-YN235	
6036	14	CQ		1-7	24-54-11	C01007	=B	D	*	C01386	=B	D		YL964-YL999, YN236-YR328	
6037	18	CQ		6-8	24-61-31	TB5180B		9	E	C01387	=B	D		YC051-YD157	
6038	12	CQ		6-6	24-61-31	C00783	=B	D	*	TB5180B	9	E		ALL	
6039	18	CQ		2-3	24-61-31	C00148	=B	D		C00783	=B	D	*	ALL	
6040	08	CQ		3-8	24-61-21	C00286	=B	D		TB5180C	4	E		ALL	
6041	10	CQ		4-1	24-61-21	TB5180C		5	E	C01365	=B	D	*	YC051-YC052	
6043	14	CQ		1-3	24-61-21	C00058	=B	D	*	C00468	=B	D	*	ALL	
6045	08	CQ		4-8	24-61-21	TB5180C		4	E	C01274	=B	D	*	YC051-YL954	
6045	08	CQ		4-8	24-61-21	TB5180C		4	E	C01274	=B	D		YN231-YN235	
6046	08	CQ		2-2	24-61-21	C00442	=B	D		C01358	=B	D		YC051-YC052	
6047	14	CQ		1-5	24-61-21	C00250	=B	D		C01434	=B	D		YC051-YL954, YN231-YN235	

WIRE LIST

D280A108

91-21-11

Section W0020

Page 4

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0020	286A0020				P18-BUS WIRING (continued)										
6047	14	CQ			1-5	24-61-21	C00250	=B	D	*	C01434	=B	D		YL955-YL999, YN236-YR328
6048	14	CQ			1-1	24-61-21	C01001	=B	D		C00054	=B	D		ALL
6049	16	PA			5-1	24-61-23	C01141	=B	D		TB5180D	1	E		YC051-YC059
6049	16	PA			5-2	24-61-23	C01141	=B	D		TB5180D	1	E		YC060-YD155
6051	12	GA			1-7	24-61-23	C01433	=B	D	*	C01404	=B	D		YC051-YC052
6051	12	HA			1-7	24-61-23	C01433	=B	D	*	C01404	=B	D		YC053-YR328
6052	16	CQ			2-7	24-51-11	C00923	=B	D	*	C01420	=B	D		YC051-YC058
6052	16	CQ			2-7	24-51-11	C01420	=B	D		C00923	=B	D		YC059, YD151-YD157
6052	16	CQ			2-7	24-51-13	C01420	=B	D		C00923	=B	D		YC060-YC070
6053	16	CQ			3-6	24-61-41	C01376	=B	D		TB5180B	1	E		YC051-YC052
6053	16	CQ			3-7	24-61-41	C01376	=B	D		TB5180B	1	E		YC053-YC058
6053	16	CQ			3-8	24-61-41	C01376	=B	D		TB5180B	1	E		YC059-YD155
6053	16	CQ			3-8	24-61-41	TB5180B	2	E		C01376	=B	D		YD157-YR328
6054	10	CQ			5-6	24-61-41	TB5180B	1	E		C01204	=B	D		YC051-YC058
6054	10	CQ			5-7	24-61-41	TB5180B	1	E		C01204	=B	D		YC059-YD155
6054	10	CQ			5-6	24-61-41	TB5180B	2	E		C01204	=B	D		YD157-YL954, YN231-YN235
6055	12	CQ			1-8	24-61-41	C01392	=B	D		C00357	=B	D	*	YC051-YD157
6056	16	CQ			2-1	24-61-41	C00357	=B	D	*	C01266	=B	D		YC051-YD157
6057	18	CQ			7-1	24-61-61	C01423	=B	D		TB5180B	5	E		YC051-YC058
6057	18	CQ			7-2	24-61-61	C01423	=B	D		TB5180B	5	E		YC059-YR328
6058	14	CQ			2-0	24-61-21	C01365	=B	D	*	C01422	=B	D	*	YC051-YC052
6059	14	CQ			2-11	24-61-21	C01422	=B	D	*	C00058	=B	D	*	YC051-YD157
6060	16	CQ			3-9	24-61-52	C01009	=B	D	*	TB5180B	2	E		YC051-YD155
6060	16	CQ			3-9	24-61-52	TB5180B	3	E		C01009	=B	D	*	YD157-YL963, YN231-YN235
6060	16	CQ			3-10	24-61-52	TB5180B	3	E		C01009	=B	D	*	YL964-YL999, YN236-YR328
6062	16	CQ			1-7	24-61-52	C01049	=B	D		C01009	=B	D	*	YC051-YL963, YN231-YN235
6062	16	CQ			1-8	24-61-52	C01049	=B	D		C01009	=B	D	*	YL964-YL999, YN236-YR328
6064	18	CQ			3-0	24-52-11	C00113	=B	D		C00163	=B	D	*	YC051-YL999
6064	18	CQ			3-0	24-52-11	C00163	=B	D	*	C00113	=B	D		YN231-YN260
6065	18	CQ			6-1	24-52-11	C00110	=B	D		TB5180C	2	E		YC051-YL999, YR301-YR328
6065	18	CQ			6-1	24-52-11	TB5180C	2	E		C00110	=B	D		YN231-YN501
6066	08	CQ			1-2	24-61-21	C01125	=B	D		C01462	=B	D	*	YL951-YL954

WIRE LIST

D280A108

91-21-11

Section W0020

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From			To					
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0020	286A0020			P18-BUS WIRING (continued)											
6066	14	CQ			1-5	24-61-21	C01125	=B	D		C01462	=B	D	*	YL955-YL999, YR301-YR328
6066	08	CQ			1-2	24-61-21	C01462	=B	D	*	C01125	=B	D		YN231-YN235
6066	14	CQ			1-5	24-61-21	C01462	=B	D	*	C01125	=B	D		YN236-YN501
6067	18	CQ			1-1	24-53-11	C00425	=B	D		C01205	=B	D		YC051-YC059
6067	18	CQ			1-1	24-53-11	C01205	=B	D		C00425	=B	D		YC060-YD170
6067	18	CQ			1-1	24-53-11	C01205	=B	D	*	C00425	=B	D		YL951-YR328
6075	10	CQ			1-0	24-53-11	C00123	=B	D		C00244	=B	D		YC051-YC053
6075	12	CQ			1-0	24-53-11	C00123	=B	D		C00244	=B	D		YC054-YD170
6075	12	CQ			1-0	24-53-11	C00123	=B	D	*	C00244	=B	D		YL951-YR328
6076	16	CQ			2-7	24-51-11	C00644	=B	D		C00911	A2	D	*	YC051-YC059
6076	16	CQ			2-7	24-51-12	C00911	A2	D	*	C00644	=B	D		YC060-YC070, YD160-YL999, YR301-YR328
6076	16	CQ			2-7	24-51-11	C00911	A2	D	*	C00644	=B	D		YD151-YD158
6077	12	CQ			4-3	24-51-11	TB5180E		7	E	C00911	A2	D	*	YC051-YC059
6077	12	CQ			4-3	24-51-12	TB5180E		7	E	C00911	A2	D	*	YC060-YL999, YR301-YR328
6078	14	CQ			1-1	24-51-11	C00700	=B	D		C00911	B2	D	*	YC051-YC059
6078	14	CQ			1-1	24-51-12	C00911	B2	D	*	C00700	=B	D		YC060-YC070, YD160-YL999, YR301-YR328
6078	14	CQ			1-1	24-51-11	C00911	B2	D	*	C00700	=B	D		YD151-YD158
6079	10	CQ			4-0	24-51-11	TB5180E		8	E	C00911	B2	D	*	YC051-YC059, YD151-YD158
6079	10	CQ			4-0	24-51-12	TB5180E		8	E	C00911	B2	D	*	YC060-YC070, YD160-YL999, YR301-YR328
6080	12	CQ			1-3	24-51-11	C00104	=B	D		C00911	C2	D	*	YC051-YC059
6080	12	CQ			1-3	24-51-12	C00911	C2	D	*	C00104	=B	D		YC060-YC070, YD160-YL999, YR301-YR328
6080	12	CQ			1-3	24-51-11	C00911	C2	D	*	C00104	=B	D		YD151-YD158
6081	10	CQ			4-1	24-51-11	TB5180E		9	E	C00911	C2	D	*	YC051-YC059, YD151-YD158
6081	10	CQ			4-1	24-51-12	TB5180E		9	E	C00911	C2	D	*	YC060-YC070, YD160-YL999, YR301-YR328
6084	14	CQ			1-5	24-61-21	C01125	=B	D		C01460	=B	D		YC053-YC059

WIRE LIST
D280A108

91-21-11
Section W0020
Page 6
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W0020	286A0020	P18-BUS WIRING (continued)			
6084	14 CQ	1-5 24-61-21	C01460 =B D	C01125 =B D	YC060-YD170
6085	14 CQ	2-4 24-61-21	C01192 =B D	C00468 =B D	YC051-YC059
6085	14 CQ	2-4 24-61-21	C00468 =B D	C01192 =B D	YC060-YR328
6086	14 PA	1-4 24-61-21	C01192 =B D	C01003 =B D	YC051-YC059
6086	14 CQ	1-4 24-61-21	C01192 =B D	C01003 =B D	YC060-YR328
6090	18 CQ	5-2 24-52-11	TB5180C 3 E	C00163 =B D	YC051-YN260
6091	08 CQ	5-2 24-53-11	C00234 =B D	TB5180B 8 E	YC051-YC058
6091	08 CQ	5-7 24-53-11	C00234 =B D	TB5180B 8 E	YC059
6091	08 CQ	5-7 24-53-11	TB5180B 8 E	C00234 =B D	YC060-YD157
6095	16 CQ	1-2 24-51-12	C01073 =B D	C01473 =B D	YN231-YN501
6096	14 CQ	5-3 24-61-21	TB5180C 5 E	C00058 =B D	YD158-YR328
6098	08 CQ	2-10 24-61-21	C01462 =B D	C01518 =B D	YL951-YL954, YN231-YN235
6098	14 CQ	3-1 24-61-21	C01462 =B D	C01518 =B D	YL955-YL999, YN236-YR328
6100	12 GA	6-0 24-61-23	C01433 =B D	TB5180D 1 E	YC051-YC052
6102	16 CQ	4-3 24-51-11	C00839 A2 D	TB5180E 2 E	YC051-YC059
6102	16 CQ	4-3 24-51-13	TB5180E 2 E	C00839 A2 D	YC060-YC070, YD160-YR328
6102	16 CQ	4-3 24-51-11	TB5180E 2 E	C00839 A2 D	YD151-YD158
6103	16 CQ	4-2 24-51-11	C00839 B2 D	TB5180E 4 E	YC051-YC059
6103	16 CQ	4-2 24-51-13	TB5180E 4 E	C00839 B2 D	YC060-YC070, YD160-YR328
6103	16 CQ	4-2 24-51-11	TB5180E 4 E	C00839 B2 D	YD151-YD158
6104	16 CQ	4-1 24-51-11	C00839 C2 D	TB5180E 6 E	YC051-YC052
6104	14 CQ	4-1 24-51-11	TB5180E 6 E	C00839 C2 D	YC053-YC058
6104	14 CQ	4-1 24-51-11	TB5180E 6 E	C00839 C2 D	YC059, YD151-YD157
6104	14 CQ	4-1 24-51-13	TB5180E 6 E	C00839 C2 D	YC060-YC070
6104	16 CQ	4-1 24-51-11	TB5180E 6 E	C00839 C2 D	YD158
6104	16 CQ	4-1 24-51-13	TB5180E 6 E	C00839 C2 D	YD160-YR328
6107	16 CQ	1-11 24-51-11	C00109 =B D	C01314 =B D	YC053-YC059, YD151-YD158
6107	16 CQ	1-11 24-51-13	C00109 =B D	C01314 =B D	YC060-YC070, YD160-YR328
6108	18 CQ	1-2 24-54-11	C00458 =B D	C01017 =B D	YC053-YD158
6108	18 CQ	1-3 24-54-11	C00458 =B D	C01017 =B D	YD160-YR328
6112	14 CQ	1-0 24-61-21	C01274 =B D	C01156 =B D	YC051-YL954
6112	14 CQ	1-0 24-61-21	C01274 =B D	C01156 =B D	YL955-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W0020

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0020	286A0020				P18-BUS WIRING (continued)										
6118	16	CQ			2-1	24-51-11	C00109	=B	D		C00839	A2	D	*	YC051-YC052
6118	16	CQ			2-1	24-51-11	C00109	=B	D	*	C00839	A2	D	*	YC053-YC059
6118	16	CQ			2-1	24-51-13	C00839	A2	D	*	C00109	=B	D	*	YC060-YC070, YD160-YR328
6118	16	CQ			2-1	24-51-11	C00839	A2	D	*	C00109	=B	D	*	YD151-YD158
6119	16	CQ			2-1	24-51-11	C01390	=B	D		C00839	B2	D	*	YC051-YC059
6119	16	CQ			2-1	24-51-13	C00839	B2	D	*	C01390	=B	D		YC060-YC070, YD160-YR328
6119	16	CQ			2-1	24-51-11	C00839	B2	D	*	C01390	=B	D		YD151-YD158
6120	16	CQ			2-6	24-51-11	C00923	=B	D	*	C00839	C2	D	*	YC051-YC058
6120	16	CQ			2-6	24-51-11	C00839	C2	D	*	C00923	=B	D		YD158
6120	16	CQ			2-6	24-51-13	C00839	C2	D	*	C00923	=B	D		YD160-YR328
6123	14	CQ			1-9	24-61-21	C00721	=B	D		C01519	=B	D		YC053-YR328
6127	14	CQ			5-3	24-61-21	TB5180C	5	E		C01422	=B	D	*	YC053-YD157
6129	16	PA			1-3	24-61-23	C00471	=B	D	*	C01537	=B	D		YC051-YD157
6129	16	HA			1-3	24-61-23	C00471	=B	D	*	C01537	=B	D		YD158-YN260
6133	08	CQ			1-1	24-61-21	C00442	=B	D		C01522	=B	D		YC053-YL954, YN231-YN235
6133	14	CQ			1-4	24-61-21	C00442	=B	D		C01522	=B	D		YL955-YL999, YN236-YR328
6134	08	CQ			2-9	24-61-21	C01524	=B	D		C01358	=B	D		YC053-YL954, YN231-YN235
6134	12	CQ			3-0	24-61-21	C01524	=B	D		C01358	=B	D	*	YL955-YL999, YN236-YR328
6135	10	HA			4-11	24-61-23	TB5180D	1	E		C01523	=B	D		YC053-YC059
6135	10	HA			5-1	24-61-23	TB5180D	1	E		C01523	=B	D		YC060-YD158
6136	12	HA			3-5	24-61-23	C01525	=B	D		C01433	=B	D	*	YC053-YR328
6137	18	CQ			7-5	24-61-51	TB5180B	10	E		C01526	=B	D		YC053-YD155
6137	18	CQ			6-8	24-61-51	TB5180F	4	E		C01526	=B	D		YD157-YR328
6139	18	CQ			5-3	24-54-11	TB5180B	3	E		C00523	=B	D		YC051-YC052
6139	18	CQ			5-4	24-54-11	TB5180B	3	E		C00523	=B	D		YC053-YD155
6139	18	CQ			4-9	24-54-11	TB5180F	2	E		C00523	=B	D		YD157-YL959, YN231-YN235
6139	18	CQ			4-10	24-54-11	TB5180F	2	E		C00523	=B	D		YL963-YL999, YN236-YR328
6147	14	CQ			4-10	24-51-13	TB5180E	5	E		C00849	C2	D		YL963-YL999, YN236-YR328
6163	12	CQ			1-7	24-61-41	C01369	=B	D		C00165	=B	D	*	YD158-YR328
6164	16	CQ			2-2	24-61-41	C00165	=B	D	*	C01266	=B	D		YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0020

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type
W0020	286A0020				P18-BUS WIRING (continued)										
6183	18	CQ		2-0	24-61-31	C01551	=B	D	*	C01103	=B	D	*	YD158-YR328	
6186	16	CQ		6-6	24-61-31	TB5180B		9	E		C01551	=B	D	*	YD158-YR328
6193	08	CQ		6-1	24-53-11	TB5180B		8	E		C01217	=B	D		YD158-YL967, YN231-YN235
6193	08	CQ		6-2	24-53-11	TB5180B		8	E		C01217	=B	D		YL968-YL999, YN236-YR328
6197	10	HA		5-2	24-61-23	TB5180D		1	E		C01657	=B	D		YD160-YL967, YN231-YN235
6197	10	HA		5-2	24-61-23	TB5180D		1	E		C01657	=B	D	*	YL968-YL999, YN236-YR328
6198	12	HA		1-0	24-61-23	C01657	=B	D		C01523	=B	D		YD160-YL967, YN231-YN235	
6206	16	CQ		6-8	24-61-41	C01680	=B	D		TB5180B		2	E		YD160-YL967, YN231-YN501
6206	16	CQ		6-8	24-61-41	C01680	=B	D	*	TB5180B		2	E		YL968-YL999, YR301-YR328
6248	18	CQ		1-4	24-61-31	C01103	=B	D		C01317	=B	D		YC051-YD157	
6248	18	CQ		1-4	24-61-31	C01103	=B	D	*	C01317	=B	D		YD158-YR328	
6262	10	CQ		0-9	24-61-21	C00250	=B	D	*	C01358	=B	D	*	YL955-YL999, YN236-YR328	
6263	08	CQ		4-11	24-61-21	TB5180C		4	E		C01357	=B	D		YL955-YL999, YN236-YR328
6264	10	CQ		5-2	24-61-41	TB5180B		1	E		C01363	=B	D		YL955-YL999, YN236-YR328
6273	16	CQ		5-2	24-52-11	TB5180C		3	E		C01648	=B	D	*	YN501-YR328
6274	18	CQ		3-0	24-52-11	C00113	=B	D		C01648	=B	D	*	YN501-YR328	
6275	16	CQ		1-4	24-61-23	C00471	=B	D		C01948	=B	D		YL963-YL999, YN236-YN260, YR301-YR328	
6275	16	CQ		1-4	24-61-23	C00471	=B	D	*	C01948	=B	D	*	YN501	
6276	16	CQ		1-0	24-61-23	C01948	=B	D	*	C01537	=B	D		YN501	
6276	16	CQ		1-0	24-61-23	C01948	=B	D		C01537	=B	D		YR301-YR328	
6280	10	HA		1-3	24-61-23	C01657	=B	D	*	C01947	=B	D	*	YL968-YL999, YN236-YR328	
6281	10	HA		1-2	24-61-23	C01947	=B	D	*	C01523	=B	D		YL968-YL999, YN236-YR328	
6283	16	CQ		2-6	24-61-41	C01680	=B	D	*	C01946	=B	D		YL968-YL999, YR301-YR328	
6283	16	CQ		2-6	24-61-41	C01680	=B	D		C01946	=B	D		YN236-YN501	

WIRE LIST

D280A108

91-21-11

Section W0020

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0020	286A0020			P18-BUS WIRING (continued)											
ZZAB	02		ZB		0-0	24-51-11	C00456	=B	D		C01041	=B	D		YC051-YC059
ZZAB	02		ZB		0-0	24-51-13	C00456	=B	D		C01041	=B	D		YC060-YR328
ZZAD	03		ZB		0-0	24-51-11	C01314	=B	D		C01238	=B	D		YC051-YC052
ZZAE	00		ZB		0-0	24-51-11	C01017	=B	D		C01314	=B	D		YC051-YC052
ZZAF	02		ZB		0-0	24-51-11	C00153	=B	D		C01390	=B	D		YC051-YC059, YD151-YD158
ZZAF	02		ZB		0-0	24-51-13	C00153	=B	D		C01390	=B	D		YC060-YC070, YD160-YR328
ZZAG	02		ZB		0-0	24-51-11	C00224	=B	D		C00227	=B	D		YC051-YC059
ZZAG	02		ZB		0-0	24-51-13	C00224	=B	D		C00227	=B	D		YC060-YR328
ZZAH	02		ZB		0-0	24-52-11	C00114	=B	D		C00113	=B	D		ALL
ZZAI	03		ZB		0-0	24-51-11	C02046	=B	D		C01072	=B	D		YC051-YC059
ZZAI	03		ZB		0-0	24-51-13	C02046	=B	D		C01072	=B	D		YC060-YR328
ZZAJ	00		ZB		0-0	24-51-11	C02046	=B	D		C00236	=B	D		YC051-YC059
ZZAJ	00		ZB		0-0	24-51-13	C02046	=B	D		C00236	=B	D		YC060-YR328
ZZAK	00		ZB		0-0	24-51-11	C00236	=B	D		C01072	=B	D		YC051-YC059, YD151-YD158
ZZAK	00		ZB		0-0	24-51-13	C00236	=B	D		C01072	=B	D		YC060-YC070, YD160-YR328
ZZAL	00		ZB		0-0	24-51-11	C00104	=B	D		C01073	=B	D		YC051-YC059, YD151-YD158
ZZAL	00		ZB		0-0	24-51-12	C00104	=B	D		C01073	=B	D		YC060-YC070, YD160-YL999, YR301-YR328
ZZAL	02		ZB		0-0	24-51-12	C00104	=B	D		C01073	=B	D		YN231-YN501
ZZAM	02		ZB		0-0	24-51-11	C00700	=B	D		C00233	=B	D		YC051-YC059
ZZAM	02		ZB		0-0	24-51-12	C00700	=B	D		C00233	=B	D		YC060-YR328
ZZAN	03		ZB		0-0	24-51-21	C00226	=B	D		C01071	=B	D		YC051-YC059, YD151-YD158
ZZAN	03		ZB		0-0	24-51-23	C00226	=B	D		C01071	=B	D		YC060-YC070, YD160-YR328
ZZAO	00		ZB		0-0	24-51-21	C00225	=B	D		C01071	=B	D		YC051-YC059, YD151-YD158
ZZAO	00		ZB		0-0	24-51-23	C00225	=B	D		C01071	=B	D		YC060-YC070, YD160-YR328
ZZAP	00		ZB		0-0	24-51-21	C00226	=B	D		C00225	=B	D		YC051-YC059, YD151-YD158
ZZAP	00		ZB		0-0	24-51-23	C00226	=B	D		C00225	=B	D		YC060-YC070, YD160-YR328

WIRE LIST

D280A108

91-21-11

Section W0020

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0020	286A0020			P18-BUS WIRING (continued)											
ZZAQ	02		ZB		0-0	24-51-21	C00525	=B	D		C00237	=B	D		YC051-YC059, YD151-YD158
ZZAQ	02		ZB		0-0	24-51-23	C00525	=B	D		C00237	=B	D		YC060-YC070, YD160-YR328
ZZAR	04		ZB		0-0	24-53-11	C01407	=B	D		C01406	=B	D		YC051-YC053
ZZAS	00		ZB		0-0	24-53-11	C01407	=B	D		C01408	=B	D		YC051-YC053
ZZAT	00		ZB		0-0	24-53-11	C01408	=B	D		C01405	=B	D		YC051-YC053
ZZAU	00		ZB		0-0	24-53-11	C01405	=B	D		C01406	=B	D		YC051-YC053
ZZAV	00		ZB		0-0	24-51-11	C01017	=B	D		C01238	=B	D		YC051-YC052
ZZAV	02		ZB		0-0	24-54-11	C01017	=B	D		C01238	=B	D		YC053-YR328
ZZAW	05		ZB		0-0	24-54-11	C01386	=B	D		C01374	=B	D		ALL
ZZAX	04		ZB		0-0	24-61-31	C00783	=B	D		C00156	=B	D		ALL
ZZAY	00		ZB		0-0	24-61-31	C00783	=B	D		C00784	=B	D		ALL
ZZAZ	00		ZB		0-0	24-61-31	C00785	=B	D		C00784	=B	D		ALL
ZZBA	00		ZB		0-0	24-61-31	C00785	=B	D		C00156	=B	D		ALL
ZZBB	06		ZB		0-0	24-61-21	C00286	=B	D		C01045	=B	D		ALL
ZZBC	00		ZB		0-0	24-61-21	C00286	=B	D		C01354	=B	D		ALL
ZZBD	00		ZB		0-0	24-61-21	C01354	=B	D		C01044	=B	D		ALL
ZZBE	00		ZB		0-0	24-61-21	C01044	=B	D		C00457	=B	D		ALL
ZZBF	00		ZB		0-0	24-61-21	C00457	=B	D		C01048	=B	D		ALL
ZZBG	00		ZB		0-0	24-61-21	C01048	=B	D		C01045	=B	D		ALL
ZZBI	02		ZB		0-0	24-61-21	C01003	=B	D		C01312	=B	D		ALL
ZZBK	02		ZB		0-0	24-61-31	C01317	=B	D		C01316	=B	D		ALL
ZZBL	05		ZB		0-0	24-61-21	C00250	=B	D		C01001	=B	D		ALL
ZZBN	00		ZB		0-0	24-51-11	C01096	=B	D		C01073	=B	D		YC051-YC059
ZZBN	00		ZB		0-0	24-51-12	C01073	=B	D		C01096	=B	D		YC060-YC070, YD160-YL999, YR301-YR328
ZZBN	00		ZB		0-0	24-51-11	C01073	=B	D		C01096	=B	D		YD151-YD158
ZZBO	04		ZB		0-0	24-51-11	C01473	=B	D		C00104	=B	D		YC051-YC059
ZZBO	04		ZB		0-0	24-51-11	C00104	=B	D		C01473	=B	D		YC060-YD158
ZZBP	02		ZB		0-0	24-61-61	C01423	=B	D		C01463	=B	D		ALL
ZZBQ	03		ZB		0-0	24-61-23	C01404	=B	D		C00149	=B	D		ALL
ZZBR	00		ZB		0-0	24-61-23	C01404	=B	D		C01002	=B	D		ALL
ZZBS	00		ZB		0-0	24-61-23	C01002	=B	D		C00149	=B	D		ALL
ZZBT	04		ZB		0-0	24-61-41	C01204	=B	D		C00412	=B	D		ALL
ZZBV	00		ZB		0-0	24-61-41	C00170	=B	D		C01392	=B	D		ALL
ZZBW	00		ZB		0-0	24-61-41	C01392	=B	D		C01204	=B	D		ALL
ZZBX	02		ZB		0-0	24-61-41	C01363	=B	D		C01359	=B	D		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W0020

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0020		286A0020			P18-BUS WIRING (continued)											
ZZBX		00		ZB		0-0	24-61-41	C01363	=B	D		C01359	=B	D		YC053-YC059
ZZBX		00		ZB		0-0	24-61-41	C01359	=B	D		C01363	=B	D		YC060-YR328
ZZBY		02		ZB		0-0	24-61-21	C01274	=B	D		C01125	=B	D		ALL
ZZBZ		02		ZB		0-0	24-61-41	C01369	=B	D		C01372	=B	D		YC051-YC052
ZZBZ		00		ZB		0-0	24-61-41	C01369	=B	D		C01372	=B	D		YC053-YC059
ZZBZ		00		ZB		0-0	24-61-41	C01372	=B	D		C01369	=B	D		YC060-YR328
ZZCA		03		ZB		0-0	24-61-41	C01266	=B	D		C00276	=B	D		ALL
ZZCB		00		ZB		0-0	24-61-41	C01266	=B	D		C01412	=B	D		ALL
ZZCD		00		ZB		0-0	24-61-41	C01412	=B	D		C00276	=B	D		ALL
ZZCE		02		ZB		0-0	24-61-41	C00165	=B	D		C00357	=B	D		YC051-YC059
ZZCE		02		ZB		0-0	24-61-41	C00357	=B	D		C00165	=B	D		YC060-YD157
ZZCH		00		ZB		0-0	24-54-11	C01378	=B	D		C01382	=B	D		ALL
ZZCI		00		ZB		0-0	24-54-11	C01382	=B	D		C01386	=B	D		ALL
ZZCJ		00		ZB		0-0	24-61-41	C01365	=B	D		C01372	=B	D		YC053-YR328
ZZCK		02		ZB		0-0	24-61-23	C00471	=B	D		C01143	=B	D		YC051-YD157
ZZCL		00		ZB		0-0	24-61-41	C00412	=B	D		C00170	=B	D		ALL
ZZCN		00		ZB		0-0	24-61-41	C01363	=B	D		C01365	=B	D		YC053-YR328
ZZCO		05		ZB		0-0	24-61-41	C01359	=B	D		C01369	=B	D		YC053-YR328
ZZCP		02		ZB		0-0	24-61-21	C01518	=B	D		C00442	=B	D		YL951-YR328
ZZCT		00		ZB		0-0	24-54-11	C01374	=B	D		C01479	=B	D		YC051-YC059
ZZCT		00		ZB		0-0	24-54-11	C01479	=B	D		C01374	=B	D		YC060-YR328
ZZCU		00		ZB		0-0	24-54-11	C01479	=B	D		C01378	=B	D		YC051-YC059
ZZCU		00		ZB		0-0	24-54-11	C01378	=B	D		C01479	=B	D		YC060-YR328
ZZCX		00		ZB		0-0	24-51-11	C01473	=B	D		C01096	=B	D		YC051-YC059
ZZCX		00		ZB		0-0	24-51-11	C01096	=B	D		C01473	=B	D		YC060-YD158
ZZDK		03		ZB		0-0	24-51-12	C00104	=B	D		C01096	=B	D		YL951-YL999, YR301-YR328 YD158-YD170, YR315-YR316, YR319
ZZDO		02		ZB		0-0	24-61-51	C01526	=B	D		C01528	=B	D		ALL
ZZEC		00		ZB		0-0	24-61-21	C01001	=B	D		C01403	=B	D		ALL
ZZED		00		ZB		0-0	24-61-21	C01357	=B	D		C00250	=B	D		ALL
ZZEF		00		ZB		0-0	24-61-21	C00073	=B	D		C01357	=B	D		ALL
ZZEG		00		ZB		0-0	24-61-21	C01403	=B	D		C00073	=B	D		ALL
ZZQA		02		ZK		0-0	24-53-11	TB5180B	7	E		TB5180B	8	E		ALL
ZZQB		02		ZK		0-0	24-61-21	TB5180C	4	E		TB5180C	5	E		ALL
ZZQC		02		ZK		0-0	24-51-11	TB5180E	1	E		TB5180E	2	E		YC051-YC059, YD151-YD158 YC060-YC070, YD160-YR328
ZZQC		02		ZK		0-0	24-51-13	TB5180E	1	E		TB5180E	2	E		

WIRE LIST

D280A108

91-21-11

Section W0020

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0020	286A0020			P18-BUS WIRING (continued)											
ZZQD	02		ZK		0-0	24-51-11	TB5180E	3	E		TB5180E	4	E		YC051-YC059, YD151-YD158
ZZQD	02		ZK		0-0	24-51-13	TB5180E	3	E		TB5180E	4	E		YC060-YC070, YD160-YR328
ZZQE	02		ZK		0-0	24-51-11	TB5180E	5	E		TB5180E	6	E		YC051-YC059, YD151-YD158
ZZQE	02		ZK		0-0	24-51-13	TB5180E	5	E		TB5180E	6	E		YC060-YC070, YD160-YR328
ZZQF	02		ZK		0-0	24-61-41	TB5180B	1	E		TB5180B	2	E		YD157-YR328
ZZQG	02		ZK		0-0	24-54-11	TB5180F	1	E		TB5180F	2	E		YD157-YR328
ZZQH	02		ZK		0-0	24-61-51	TB5180F	3	E		TB5180F	4	E		YD157-YR328
ZZXB	02		ZA		0-0	24-51-11	C01041	=B	D		C01384	=B	D		YC051-YC059, YD151-YD158
ZZXB	02		ZA		0-0	24-51-13	C01041	=B	D		C01384	=B	D		YC060-YC070, YD160-YR328
ZZXC	02		ZA		0-0	24-51-11	C00849	A2	D		C00456	=B	D		YC051-YC059, YD151-YD158
ZZXC	02		ZA		0-0	24-51-13	C00849	A2	D		C00456	=B	D		YC060-YC070, YD160-YR328
ZZXD	02		ZA		0-0	24-51-11	C00190	=B	D		C01195	=B	D		YC051-YC052
ZZXE	02		ZA		0-0	24-51-11	C00849	B2	D		C00190	=B	D		YC051-YC052
ZZXF	02		ZA		0-0	24-51-11	C00849	C2	D		C01429	=B	D		YC051-YC059, YD151-YD158
ZZXF	02		ZA		0-0	24-51-13	C00849	C2	D		C01429	=B	D		YC060-YC070, YD160-YL959, YN231-YN235
ZZXH	02		ZA		0-0	24-51-11	C01384	=B	D		C00629	=B	D		YC051-YC059
ZZXH	02		ZA		0-0	24-51-13	C00629	=B	D		C01384	=B	D		YC060-YC070, YD160-YR328
ZZXH	02		ZA		0-0	24-51-11	C00629	=B	D		C01384	=B	D		YD151-YD158
ZZXI	02		ZA		0-0	24-51-11	C00109	=B	D		C01238	=B	D		YC051-YC052
ZZXJ	02		ZA		0-0	24-54-11	C00186	=B	D		C00190	=B	D		YC053-YR328
ZZXK	02		ZA		0-0	24-51-11	C00111	=B	D		C00274	=B	D		YC051-YC059, YD151-YD158
ZZXK	02		ZA		0-0	24-51-13	C00111	=B	D		C00274	=B	D		YC060-YC070, YD160-YR328
ZZXN	02		ZA		0-0	24-51-11	C00115	=B	D		C00271	=B	D		YC051-YC059, YD151-YD158

WIRE LIST

D280A108

91-21-11

Section W0020

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0020	286A0020			P18-BUS WIRING (continued)											
ZZXN	02		ZA		0-0	24-51-13	C00115	=B	D		C00271	=B	D		YC060-YC070, YD160-YR328
ZZXP	02		ZA		0-0	24-53-11	C00244	=B	D		C01407	=B	D		ALL
ZZXQ	02		ZA		0-0	24-61-31	C01387	=B	D		C01103	=B	D		YC051-YD157
ZZXR	02		ZA		0-0	24-61-21	C00721	=B	D		C01045	=B	D		YC051-YD155
ZZXS	02		ZA		0-0	24-61-21	C01125	=B	D		C00442	=B	D		YC051-YD170
ZZXT	02		ZA		0-0	24-61-21	C01358	=B	D		C01357	=B	D		YC051-YL954, YN231-YN235
ZZXV	02		ZA		0-0	24-61-21	C01045	=B	D		C01629	=B	D		YD157-YR328
ZZXW	02		ZA		0-0	24-61-21	C01629	=B	D		C00721	=B	D		YD157-YR328
ZZXX	02		ZA		0-0	24-61-41	C01359	=B	D		C00412	=B	D		YC051-YD170, YN231-YN501
ZZXX	02		ZA		0-0	24-61-41	C00412	=B	D		C01359	=B	D		YL951-YL999, YR301-YR328
ZZXY	02		ZA		0-0	24-61-41	C01372	=B	D		C01363	=B	D		YC051-YC052
ZZXZ	02		ZA		0-0	24-61-23	C00149	=B	D		C00055	=B	D		ALL
ZZYA	02		ZA		0-0	24-51-11	C01195	=B	D		C00849	B2	D		YC053-YC059, YD151-YD158
ZZYA	02		ZA		0-0	24-51-13	C01195	=B	D		C00849	B2	D		YC060-YC070, YD160-YR328
ZZYF	02		ZA		0-0	24-54-11	C00186	=B	D		C01374	=B	D		YC051-YC059
ZZYF	02		ZA		0-0	24-54-11	C01374	=B	D		C00186	=B	D		YC060-YR328
ZZYI	02		ZA		0-0	24-51-12	C01096	=B	D		C01473	=B	D		YL951-YL999, YR301-YR328
ZZYK	02		ZA		0-0	24-61-21	C01522	=B	D		C01524	=B	D		YC053-YR328
ZZYL	02		ZA		0-0	24-61-23	C01523	=B	D		C01525	=B	D		YC053-YR328
ZZYO	02		ZA		0-0	24-53-11	C00245	=B	D		C01408	=B	D		YC054-YR328
ZZYP	02		ZA		0-0	24-53-11	C01408	=B	D		C01406	=B	D		YC054-YR328
ZZYQ	02		ZA		0-0	24-53-11	C01407	=B	D		C01405	=B	D		YC054-YR328
ZZYU	02		ZA		0-0	24-51-11	C00839	C2	D		C01420	=B	D		YC059, YD151-YD157
ZZYU	02		ZA		0-0	24-51-13	C00839	C2	D		C01420	=B	D		YC060-YC070
W0024	286A0024			P15 REFUELING PANEL											
0001	20		HL		1-8	28-44-11	D11320				GD00722	ST..	E		YC051-YL954, YN231-YN235
0002	20		HL		1-5	28-44-11	D11322				GD00722	ST..	E		YC051-YL954, YN231-YN235
0003	20		HL		1-7	28-44-11	D11318				GD00722	ST..	E		YC051-YL954, YN231-YN235

WIRE LIST
D280A108

91-21-11
Section W0020
Page 14
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0024	286A0024				P15 REFUELING PANEL (continued)										
0004	20		HL		1-11	28-44-11	D11320	10			S00158	3	C		YC051-YL954, YN231-YN235
0005	20		HL		2-2	28-44-11	D11320	23			GD00578	DC..	1A		YC051-YL954, YN231-YN235
0006	20		HL		2-3	28-44-11	D11322	23			GD00578	DC..	1A		YC051-YL954, YN231-YN235
0007	20		HL		2-5	28-44-11	D11318	23			GD00578	DC..	1A		YC051-YL954, YN231-YN235
0008	20		HL		2-4	28-44-11	D11322	10			S00159	3	C		YC051-YL954, YN231-YN235
0009	20		HL		1-8	28-44-11	D11320	2			S00160	5	I		YC051-YL954, YN231-YN235
0010	20		HL		1-4	28-44-11	D11320	24			SM00001		9		YC051-YL954, YN231-YN235
0011	20		HL		1-9	28-44-11	D11322	2			S00160	11	I		YC051-YL954, YN231-YN235
0012	20		HL		1-3	28-44-11	D11322	24			SM00001		9		YC051-YL954, YN231-YN235
0013	20		HL		2-0	28-44-11	D11318	2			S00160	2	I		YC051-YL954, YN231-YN235
0014	20		HL		1-5	28-44-11	D11318	24			SM00001		9		YC051-YL954, YN231-YN235
0015	20		HL		1-3	28-44-11	D04578P	21			SM00001		9		YC051-YL954, YN231-YN235
0016	20		HL		1-0	28-44-11	L00282	3	B	*	S00157	2	C		YC051-YL954, YN231-YN235
0017	20		HL		2-0	28-44-11	D04578P	12			L00283	3	B	*	YC051-YL954, YN231-YN235
0018	20		HL		1-0	28-44-11	GD00578	DC..	1A		L00282	1	B		YC051-YL954, YN231-YN235
0019	20		HL		1-0	28-44-11	GD00578	DC..	1A		L00284	1	B		YC051-YL954, YN231-YN235
0020	20		HL		1-0	28-44-11	L00282	3	B	*	S00159	2	C	*	YC051-YL954, YN231-YN235
0021	20		HL		2-2	28-44-11	D04578P	8			L00282	2	B		YC051-YL954, YN231-YN235
0022	20		HL		1-8	28-44-11	D04578P	1			D11318	11			YC051-YL954, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W0020

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To					
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W0024	286A0024				P15 REFUELING PANEL (continued)											
0023	20		HL		1-3	28-44-11	GD00578	DC..	1A		L00283	1	B		YC051-YL954, YN231-YN235	
0024	20		HL		1-9	28-44-11	D04578P		14		D11322	11			YC051-YL954, YN231-YN235	
0025	20		HL		1-1	28-44-11	L00284		3	B	*	S00159	2	C	*	YC051-YL954, YN231-YN235
0026	20		HL		1-2	28-44-11	L00284		3	B	*	S00158	2	C	*	YC051-YL954, YN231-YN235
0027	20		HL		2-2	28-44-11	D04578P		18		L00284	2	B		YC051-YL954, YN231-YN235	
0028	20		HL		2-0	28-44-11	D04578P		7		D11320	11			YC051-YL954, YN231-YN235	
0029	20		HL		2-0	28-44-11	D04578P		9		L00283	2	B		YC051-YL954, YN231-YN235	
0030	20		HL		1-0	28-44-11	S00158		2	C	*	L00283	3	B	*	YC051-YL954, YN231-YN235
0031	20		HL		1-5	28-44-11	GD00578	DC..	1A		S00160	7	I		YC051-YL954, YN231-YN235	
0032	20		HL		1-5	28-44-11	S00160		6	I		GD00578	DC..	1A		YC051-YL954, YN231-YN235
0033	20		HL		1-5	28-44-11	S00160		12	I		GD00578	DC..	1A		YC051-YL954, YN231-YN235
0034	20		HL		1-5	28-44-11	S00160		3	I		GD00578	DC..	1A		YC051-YL954, YN231-YN235
0036	20		HL		2-3	28-44-11	D04578P		10		GD00578	DC..	1A		YC051-YL954, YN231-YN235	
0037	20		HL		1-9	28-44-11	D04578P		16		S00160	8	I	*	YC051-YL954, YN231-YN235	
0038	20		HL		1-9	28-44-11	D04578P		11		S00160	8	I	*	YC051-YL954, YN231-YN235	
0039	20		HL		1-0	28-44-11	D11320		6		SM00007		9		YC051-YL954, YN231-YN235	
0040	20		HL		1-0	28-44-11	D11320		7		SM00007		9		YC051-YL954, YN231-YN235	
0041	20		HL		1-0	28-44-11	D11320		14		SM00007		9		YC051-YL954, YN231-YN235	
0042	20		HL		1-0	28-44-11	D11320		8		SM00008		9		YC051-YL954, YN231-YN235	

WIRE LIST
D280A108

91-21-11
Section W0020
Page 16
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W0024	286A0024				P15 REFUELING PANEL (continued)											
0043	20		HL		1-0	28-44-11	D11320		15			SM00008		9		YC051-YL954, YN231-YN235
0044	20		HL		1-0	28-44-11	D11320		16			SM00008		9		YC051-YL954, YN231-YN235
0045	20		HL		1-1	28-44-11	D11322		6			SM00009		9		YC051-YL954, YN231-YN235
0046	20		HL		1-1	28-44-11	D11322		7			SM00009		9		YC051-YL954, YN231-YN235
0047	20		HL		1-1	28-44-11	D11322		14			SM00009		9		YC051-YL954, YN231-YN235
0048	20		HL		1-1	28-44-11	D11322		15			SM00009		9		YC051-YL954, YN231-YN235
0049	20		HL		0-7	28-44-11	D11322		8			D11322	16			YC051-YL954, YN231-YN235
0051	20		HL		1-0	28-44-11	D11318		6			SM00011		9		YC051-YL954, YN231-YN235
0052	20		HL		1-0	28-44-11	D11318		8			SM00011		9		YC051-YL954, YN231-YN235
0053	20		HL		1-0	28-44-11	D11318		14			SM00011		9		YC051-YL954, YN231-YN235
0054	20		HL		1-0	28-44-11	D11318		15			SM00011		9		YC051-YL954, YN231-YN235
0055	20		HL		0-7	28-44-11	D11318		7			D11318	16			YC051-YL954, YN231-YN235
0060	20		HL		2-6	28-44-11	D11318		10			S00157	3	C		YC051-YL954, YN231-YN235
2001B	20		HQ	AA	1-6	28-44-11	D11320		17			SM00003		9		YC051-YL954, YN231-YN235
2001R	20		HQ	AA	0-0	28-44-11	D11320		18			SM00002		9		YC051-YL954, YN231-YN235
2001Z				AA	0-0	28-44-11	D11320		S/R			SM00002	REF		AA	YC051-YL954, YN231-YN235
2002B	20		HQ	AB	1-8	28-44-11	D11322		17			SM00003		9		YC051-YL954, YN231-YN235
2002R	20		HQ	AB	0-0	28-44-11	D11322		18			SM00002		9		YC051-YL954, YN231-YN235
2002Z				AB	0-0	28-44-11	D11322		S/R			SM00002	REF		AA	YC051-YL954, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W0020

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0024	286A0024				P15 REFUELING PANEL (continued)										
2003B	20	HQ	AC		1-10	28-44-11	D11318	17			SM00003		9		YC051-YL954, YN231-YN235
2003R	20	HQ	AC		0-0	28-44-11	D11318	18			SM00002		9		YC051-YL954, YN231-YN235
2003Z			AC		0-0	28-44-11	D11318	S/R			SM00002	REF		AA	YC051-YL954, YN231-YN235
2004B	20	HQ	AD		1-8	28-44-11	D04578P	5			SM00003		9		YC051-YL954, YN231-YN235
2004R	20	HQ	AD		0-0	28-44-11	D04578P	4			SM00002		9		YC051-YL954, YN231-YN235
2004Z			AD		0-0	28-44-11	D04578P	S/R			SM00002	REF		AA	YC051-YL954, YN231-YN235
W0028	286A0028				P28 APU REMOTE CONTROL PANEL										
0001R	20	QZ			2-0	26-11-31	D48080J	13			L00315	=P	BK		YC051-YD158
0002R	20	QZ			2-0	26-11-31	D48080J	10			L00315	=G	C		YC051-YD158
0003R	20	QZ			2-0	26-21-11	D48080J	8			S00015	1	C		YC051-YD158
A-D					0-0	26-21-11	D48080J	7			S00016	4			YC051-YD158
A-F					0-0	26-21-11	S00016	6			S00015	2	C		YC051-YD158
A-G					0-0	24-22-31	D48080J	15			S00016	1			YC051-YD158
A-H					0-0	24-22-31	D48080J	16			S00016	2			YC051-YD158
A-K					0-0	49-62-11	D48080J	1			S00016	10			YC051-YD158
A-L					0-0	49-62-11	S00016	11			S00016	CAP	Y		YC051-YD158
A-M					0-0	49-62-11	D48080J	2			S00016	12			YC051-YD158
A-R					0-0	26-11-31	D48080J	11			S00019	=C			YC051-YD158
A-S					0-0	26-11-31	D48080J	12			S00019	=NO			YC051-YD158
A-T					0-0	26-21-11	S00016	7			S00016	CAP	Y		YC051-YD158
A-U					0-0	26-21-11	S00016	9			S00016	CAP	Y		YC051-YD158

WIRE LIST

D280A108

91-21-11

Section W0020

Page 18 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W0040	286A0040				P6 (BUS SIDE)											
0004	14	CQ		4-3	24-51-11	TB5060F	1	E			C02029	=B	D	*	YC051-YC059	
0004	14	CQ		4-3	24-51-14	TB5060F	1	E			C02029	=B	D	*	YC060-YR328	
0005	14	CQ		4-5	24-51-14	TB5060F	3	E			C00399	=B	D		YN231-YN501	
0006	14	CQ		4-6	24-51-14	TB5060F	5	E			C00268	=B	D		YN231-YN501	
0007	14	CQ		2-2	24-51-11	C00259	=B	D			C02029	=B	D	*	YC051-YC059	
0007	14	CQ		2-2	24-51-14	C00259	=B	D			C02029	=B	D	*	YC060-YR328	
0008	14	CQ		6-3	24-51-11	TB5060F	2	E			C00229	=B	D		YC051-YD158	
0009	12	CQ		6-3	24-51-11	TB5060F	4	E			C00228	=B	D		YC051-YC059	
0009	12	CQ		6-3	24-51-14	TB5060F	4	E			C00228	=B	D		YC060-YL954, YN231-YN235	
0009	12	CQ		6-3	24-51-14	TB5060F	4	N			C00228	=B	M		YL955-YL999, YN236-YR328	
0010	14	CQ		6-2	24-51-11	TB5060F	6	E			C00393	=B	D		YC051-YC059	
0010	14	CQ		6-2	24-51-14	TB5060F	6	E			C00393	=B	D		YC060-YL954, YN231-YN235	
0010	14	CQ		6-2	24-51-14	TB5060F	6	N			C00393	=B	M		YL955-YL999, YN236-YR328	
0025	08	HA		4-6	24-61-24	TB5060D	9	E			TB5060G	7	E		ALL	
0039	10	HA		3-7	24-51-21	TB5060E	7	E			TB5060G	4	E		YC051-YC059, YD151-YD158	
0039	10	HA		3-7	24-51-22	TB5060E	7	E			TB5060G	4	E		YC060-YC070, YD160-YR328	
0040	10	HA		3-7	24-51-21	TB5060E	8	E			TB5060G	5	E		YC051-YC059, YD151-YD158	
0040	10	HA		3-7	24-51-22	TB5060E	8	E			TB5060G	5	E		YC060-YC070, YD160-YR328	
0041	10	HA		3-8	24-51-21	TB5060E	9	E			TB5060G	6	E		YC051-YC059, YD151-YD158	
0041	10	HA		3-8	24-51-22	TB5060E	9	E			TB5060G	6	E		YC060-YC070, YD160-YR328	
0042	08	HA		3-10	24-51-21	TB5060G	1	E			TB5060E	1	E		YC051-YC059	
0042	08	HA		3-10	24-51-24	TB5060G	1	E			TB5060E	1	E		YC060-YD158, YL951-YR328	
0043	08	HA		3-9	24-51-21	TB5060G	2	E			TB5060E	3	E		YC051-YC059	
0043	08	HA		3-9	24-51-24	TB5060G	2	E			TB5060E	3	E		YC060-YD158, YL951-YR328	
0044	08	HA		3-8	24-51-21	TB5060G	3	E			TB5060E	5	E		YC051-YC059	
0044	08	HA		3-8	24-51-24	TB5060G	3	E			TB5060E	5	E		YC060-YD158, YL951-YR328	

WIRE LIST

D280A108

91-21-11

Section W0040

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0040	286A0040				P6 (BUS SIDE) (continued)											
0045	10		CQ		4-5	24-51-11		TB5060F	1	E		TB5060H	1	E		YC051-YC059
0045	10		CQ		4-5	24-51-14		TB5060F	1	E		TB5060H	1	E		YC060-YR328
0046	10		CQ		4-3	24-51-11		TB5060F	3	E		TB5060H	2	E		YC051-YC059
0046	10		CQ		4-3	24-51-14		TB5060F	3	E		TB5060H	2	E		YC060-YR328
0047	10		CQ		4-3	24-51-11		TB5060F	5	E		TB5060H	3	E		YC051-YC059
0047	10		CQ		4-3	24-51-14		TB5060F	5	E		TB5060H	3	E		YC060-YR328
0048	10		CQ		4-4	24-61-22		TB5060F	9	E		TB5060H	6	E		ALL
0097	14		CQ		2-1	24-61-22		C00799	=B	D		C01514	=B	D		ALL
0098	14		HA		1-7	24-61-24		C01447	=B	D		C01515	=B	D		YC051-YD153, YD157-YR328
0098	14		HA		1-7	24-61-24		C01447	=B	D		C01515	=B	D	*	YD154-YD155
0200	08		CQ		12-0	24-51-11		TB5060H	1	E		R00916	A2	E		YC051-YC059, YD151-YD157
0200	08		CQ		12-0	24-51-15		TB5060H	1	E		R00916	A2	E		YC060-YC070
0200	08		CQ		8-11	24-51-11		TB5060H	1	E		R00916	A2	E		YD158
0201	08		CQ		12-0	24-51-11		TB5060H	2	E		R00916	B2	E		YC051-YC059, YD151-YD157
0201	08		CQ		12-0	24-51-15		TB5060H	2	E		R00916	B2	E		YC060-YC070
0201	08		CQ		8-11	24-51-11		TB5060H	2	E		R00916	B2	E		YD158
0202	08		CQ		12-0	24-51-11		TB5060H	3	E		R00916	C2	E		YC051-YC059, YD151-YD157
0202	08		CQ		12-0	24-51-15		TB5060H	3	E		R00916	C2	E		YC060-YC070
0202	08		CQ		8-11	24-51-11		TB5060H	3	E		R00916	C2	E		YD158
0203	08		CQ		7-0	24-51-11		R00916	A1	E		TB5060K	1	E		YC051-YC059, YD151-YD157
0203	08		CQ		7-0	24-51-15		R00916	A1	E		TB5060K	1	E		YC060-YC070
0203	08		CQ		4-11	24-51-11		R00916	A1	E		TB5060K	1	E		YD158
0203	08		CQ		4-11	24-51-15		R00916	A1	E		TB5060K	1	E		YD160-YR328
0204	08		CQ		7-0	24-51-11		R00916	B1	E		TB5060K	3	E		YC051-YC059, YD151-YD157
0204	08		CQ		7-0	24-51-15		R00916	B1	E		TB5060K	3	E		YC060-YC070
0204	08		CQ		5-0	24-51-11		R00916	B1	E		TB5060K	3	E		YD158
0204	08		CQ		5-1	24-51-15		R00916	B1	E		TB5060K	3	E		YD160-YR328
0205	08		CQ		7-0	24-51-11		R00916	C1	E		TB5060K	5	E		YC051-YC059, YD151-YD157
0205	08		CQ		7-0	24-51-15		R00916	C1	E		TB5060K	5	E		YC060-YC070
0205	08		CQ		5-2	24-51-11		R00916	C1	E		TB5060K	5	E		YD158
0205	08		CQ		5-2	24-51-15		R00916	C1	E		TB5060K	5	E		YD160-YR328

WIRE LIST

D280A108

91-21-11

Section W0040

Page 2

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W0040	286A0040				P6 (BUS SIDE) (continued)											
0206	08		HA		8-0	24-51-21		TB5060G	1	E		R00917	A2	E		YC051-YC059, YD151-YD157
0206	08		HA		8-0	24-51-25		TB5060G	1	E		R00917	A2	E		YC060-YC070
0206	08		HA		5-2	24-51-21		TB5060G	1	E		R00917	A2	E		YD158
0207	08		HA		8-0	24-51-21		TB5060G	2	E		R00917	B2	E		YC051-YC059, YD151-YD157
0207	08		HA		8-0	24-51-25		TB5060G	2	E		R00917	B2	E		YC060-YC070
0207	08		HA		5-2	24-51-21		TB5060G	2	E		R00917	B2	E		YD158
0208	08		HA		8-0	24-51-21		TB5060G	3	E		R00917	C2	E		YC051-YC059, YD151-YD157
0208	08		HA		8-0	24-51-25		TB5060G	3	E		R00917	C2	E		YC060-YC070
0208	08		HA		5-6	24-51-21		TB5060G	3	E		R00917	C2	E		YD158
0209	08		HA		5-0	24-51-21		R00917	A1	E		TB5060K	7	E		YC051-YC059, YD151-YD157
0209	08		HA		5-0	24-51-25		R00917	A1	E		TB5060K	7	E		YC060-YC070
0209	08		HA		2-10	24-51-21		R00917	A1	E		TB5060K	7	E		YD158
0209	08		HA		2-11	24-51-25		R00917	A1	E		TB5060K	7	E		YD160-YR328
0210	08		HA		5-0	24-51-21		R00917	B1	E		TB5060K	9	E		YC051-YC059, YD151-YD157
0210	08		HA		5-0	24-51-25		R00917	B1	E		TB5060K	9	E		YC060-YC070
0210	08		HA		3-0	24-51-21		R00917	B1	E		TB5060K	9	E		YD158
0210	08		HA		3-0	24-51-25		R00917	B1	E		TB5060K	9	E		YD160-YR328
0211	08		HA		5-0	24-51-21		R00917	C1	E		TB5060K	11	E		YC051-YC059
0211	08		HA		5-0	24-51-25		R00917	C1	E		TB5060K	11	E		YC060-YD157
0211	08		HA		3-1	24-51-21		R00917	C1	E		TB5060K	11	E		YD158
0211	08		HA		3-2	24-51-25		R00917	C1	E		TB5060K	11	E		YD160-YR328
0218	08		CQ		7-4	24-51-15		TB5060L	1	E		R00916	A2	E		YL951-YR328
0219	08		CQ		7-4	24-51-15		TB5060L	2	E		R00916	B2	E		YL951-YR328
0220	08		CQ		7-4	24-51-15		TB5060L	3	E		R00916	C2	E		YL951-YR328
0221	08		HA		4-4	24-51-25		TB5060L	10	E		R00917	A2	E		YL951-YR328
0222	08		HA		4-3	24-51-25		TB5060L	11	E		R00917	B2	E		YL951-YR328
0223	08		HA		4-4	24-51-25		TB5060L	12	E		R00917	C2	E		YL951-YR328
0501	12		CQ		11-3	24-54-11		TB5060C	6	E		TB5180B	3	E		YC051-YD155
0501	12		CQ		11-10	24-54-11		TB5060C	6	E		TB5180F	1	E		YD157-YR328
0502	12		CQ		10-11	24-61-31		TB5060C	4	E		TB5180B	9	E		ALL
0503	10		CQ		10-11	24-61-41		TB5060C	3	E		TB5180B	1	E		ALL
0504	10		CQ		11-0	24-61-52		TB5060C	1	E		TB5180B	2	E		YC051-YD155
0504	10		CQ		10-11	24-61-52		TB5060C	1	E		TB5180B	3	E		YD157-YR328
0505	12		CQ		11-8	24-53-11		TB5060D	4	E		TB5180B	6	E		ALL

WIRE LIST

D280A108

91-21-11

Section W0040

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type
W0040	286A0040			P6 (BUS SIDE) (continued)										
0506	08	CQ		11-0	24-53-11	TB5060D	5	E		TB5180B	8	E		ALL
0507	10	HA		10-3	24-53-11	TB5060B	3	E		TB5180B	4	E		YC051-YN236, YN501-YR316
0507	10	HA		10-3	24-53-11	TB5060B	3	E	*	TB5180B	4	E		YR317-YR328
0508	18	CQ		11-3	24-61-61	TB5060C	2	E		TB5180B	5	E		YC051-YC061
0508	18	CQ		11-1	24-61-61	TB5060C	9	E		TB5180B	5	E		YC062-YR316
0508	18	CQ		11-1	24-61-61	TB5060C	9	E	*	TB5180B	5	E		YR317-YR328
0509	14	CQ		7-1	24-51-11	TB5060F	2	E		C00744	=B	D		YC051-YC059, YD151-YD157
0509	14	CQ		7-1	24-51-14	TB5060F	2	E		C00744	=B	D		YC060-YC070
0511	14	CQ		4-5	24-51-11	TB5060F	5	E		C01170	=B	D		YC051-YC059, YD151-YD158
0511	14	CQ		4-5	24-51-14	TB5060F	5	E		C01170	=B	D		YC060-YC070, YD160-YL999, YR301-YR328
0512	14	CQ		3-11	24-51-11	TB5060F	3	E		C01159	=B	D	*	YC051-YC059, YD151-YD158
0512	14	CQ		3-11	24-51-14	TB5060F	3	E		C01159	=B	D	*	YC060-YC070, YD160-YL999, YR301-YR328
0515	18	CQ		10-9	24-61-51	TB5060C	8	E		TB5180B	10	E		YC053-YD151
0515	12	CQ		10-9	24-61-51	TB5060C	8	E		TB5180B	10	E		YD152-YD155
0515	12	CQ		11-8	24-61-51	TB5060C	8	E		TB5180F	3	E		YD157-YR328
6002	14	CQ		1-8	24-61-22	C00132	=B	D	*	C01356	=B	D	*	ALL
6003	18	CQ		6-5	24-61-32	C00082	=B	D		TB5060D	2	E		YC051-YC059
6003	16	CQ		6-5	24-61-32	TB5060D	2	E		C00082	=B	D	*	YC060-YR328
6005	18	CQ		6-0	24-54-11	TB5060C	5	E		C01425	=B	D		YC051-YN236, YN501-YR316
6005	18	CQ		6-0	24-54-11	TB5060C	5	E	*	C01425	=B	D		YR317-YR328
6007	14	CQ		1-2	24-51-11	C01157	=B	D		C00399	=B	D	*	YC051-YC059, YD151-YD158
6007	14	CQ		1-2	24-51-14	C01157	=B	D		C00399	=B	D	*	YC060-YC070, YD160-YL999, YR301-YR323, YR325-YR328
6008	14	CQ		1-6	24-51-11	C00399	=B	D	*	C01159	=B	D	*	YC051-YC059, YD151-YD158

WIRE LIST
D280A108

91-21-11
Section W0040
Page 4
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type
W0040	286A0040				P6 (BUS SIDE) (continued)										
6008	14	CQ			1-6	24-51-14	C00399	=B	D	*	C01159	=B	D	*	YC060-YC070, YD160-YL999, YR301-YR323, YR325-YR328
6009	14	HA			1-1	24-51-21	C00400	=B	D		C01167	=B	D		YC051-YC059, YD151-YD158
6009	14	HA			1-1	24-51-24	C00400	=B	D		C01167	=B	D		YC060-YC070, YD160-YL999, YR301-YR323, YR325-YR328
6010	14	HA			1-6	24-51-21	C02043	=B	D		C01162	=B	D		YC051-YC059, YD151-YD153
6010	14	HA			1-6	24-51-24	C02043	=B	D		C01162	=B	D		YC060-YC070
6010	14	HA			1-6	24-51-21	C02043	=B	D	*	C01162	=B	D	*	YD154-YD158
6010	14	HA			1-6	24-51-24	C02043	=B	D	*	C01162	=B	D	*	YD160-YL999, YR301-YR328
6011	14	HA			1-1	24-51-21	C01163	=B	D	*	C00077	=B	D	*	YC051-YC059
6011	14	HA			1-1	24-51-24	C00077	=B	D	*	C01163	=B	D	*	YC060-YC070, YD160-YL999, YR301-YR328
6011	14	HA			1-1	24-51-21	C00077	=B	D	*	C01163	=B	D	*	YD151-YD158
6012	14	HA			1-1	24-51-21	C01163	=B	D	*	C01160	=B	D		YC051-YC059, YD151-YD158
6012	14	HA			1-1	24-51-24	C01163	=B	D	*	C01160	=B	D		YC060-YC070, YD160-YL999, YR301-YR328
6013	18	CQ			1-0	24-61-32	C01444	=B	D		C01169	=B	D		YC051-YL999, YR301-YR328
6014	12	CQ			1-8	24-61-32	C01176	=B	D		C01286	=B	D		YC051-YL999, YR301-YR328
6015	14	HA			1-5	24-61-24	C01161	=B	D		C01116	=B	D		YC051-YC059
6015	14	HA			1-5	24-61-24	C01116	=B	D		C01161	=B	D		YC060-YD157, YL951-YL999, YR301-YR328
6016	12	HA			2-1	24-61-24	C00076	=B	D		C01023	=B	D		YC051-YC052
6016	12	HA			2-1	24-61-24	C01023	=B	D		C00076	=B	D		YC060-YC064
6017	12	HA			1-2	24-61-24	C01271	=B	D		C01023	=B	D		YC051-YC052, YC060-YC064
6017	10	HA			4-0	24-61-24	C01271	=B	D		C01023	=B	D		YC053-YC059

WIRE LIST

D280A108

91-21-11

Section W0040

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity			
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice	
W0040	286A0040				P6 (BUS SIDE) (continued)											
6017	10		HA		0-11	24-61-24	C01271	=B	D	*	C01023	=B	D	*	YC065-YL999, YR301-YR328	
6018	16		CQ		1-6	24-61-22	C01158	=B	D		C01117	=B	D		YC051-YL999, YR301-YR328	
6021	14		HA		1-6	24-61-24	C01116	=B	D		C00266	=B	D		YN231-YN501	
6022	14		HA		1-5	24-61-24	C01436	=B	D		C01172	=B	D		YC051-YC059	
6022	14		HA		1-5	24-61-24	C01172	=B	D		C01436	=B	D		YC060-YL999, YR301-YR328	
6022	14		HA		1-6	24-61-24	C00124	=B	D		C01436	=B	D		YN231-YN501	
6023	18		CQ		6-9	24-61-61	C01435	=B	D		TB5060C	2	E		YC051-YC061	
6023	18		CQ		6-6	24-61-61	TB5060C		10	E	C01435	=B	D		YC062-YN236, YN501-YR316	
6023	18		CQ		6-6	24-61-61	TB5060C		10	E	*	C01435	=B	D		YR317-YR328
6024	14		HA		1-9	24-61-24	C01471	=B	D	*	C01401	=B	D		YC051-YD157	
6025	14		CQ		1-11	24-61-51	C01472	=B	D	*	C01346	=B	D	*	ALL	
6036	10		PA		0-11	24-61-24	C00166	=B	D		C01450	=B	D		YC051-YC059	
6036	10		HA		0-11	24-61-24	C01450	=B	D		C00166	=B	D		YC060-YD170	
6036	10		HA		0-11	24-61-24	C01450	=B	D	*	C00166	=B	D		YL951-YN260	
6037	10		GA		1-2	24-61-24	C01450	=B	D		C01360	=B	D		YC051-YC059	
6037	08		HA		1-2	24-61-24	C01360	=B	D		C01450	=B	D		YC060-YD170	
6037	08		HA		1-2	24-61-24	C01360	=B	D		C01450	=B	D	*	YL951-YN260	
6039	14		CQ		4-11	24-53-11	C00331	=B	D		TB5060D	5	E		ALL	
6040	16		HA		4-8	24-53-11	C00426	=B	D	*	TB5060B	3	E		YC051-YN236, YN501-YR316	
6040	16		HA		4-8	24-53-11	C00426	=B	D	*	TB5060B	3	E	*1	YR317-YR328	
6041	16		HA		5-0	24-53-11	C00788	=B	D	*	TB5060B	2	E		ALL	
6042	10		HA		6-2	24-53-11	C00323	=B	D		TB5060B	3	E		YC051-YN236, YN501-YR316	
6042	10		HA		6-2	24-53-11	C00323	=B	D		TB5060B	3	E	*1	YR317-YR328	
6043	16		HA		7-7	24-53-11	C01273	=B	D		TB5060B	3	E	*	YC051-YN236, YN501-YR316	
6043	16		HA		7-7	24-53-11	C01273	=B	D		TB5060B	3	E	*	YR317-YR328	
6044	16		HA		2-1	24-53-11	C01207	=B	D		C00426	=B	D	*	ALL	
6046	14		HA		1-10	24-51-24	C00077	=B	D		C02043	=B	D	*	YN231-YN501	
6047	18		CQ		4-9	24-53-11	C00701	=B	D		TB5060D	4	E		ALL	
6048	18		CQ		3-5	24-54-11	C00459	=B	D		TB5060C	5	E		YC051-YN236, YN501-YR316	
6048	18		CQ		3-5	24-54-11	C00459	=B	D		TB5060C	5	E	*	YR317-YR328	
6049	16		CQ		6-8	24-54-11	C02047	=B	D		TB5060C	5	E		ALL	

WIRE LIST

D280A108

91-21-11

Section W0040

Page 6

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W0040	286A0040				P6 (BUS SIDE) (continued)											
6050	12		CQ		5-1	24-61-32	C00348	=B	D	*		TB5060D	1	E		ALL
6052	12		CQ		5-2	24-61-32	C01287	=B	D			TB5060D	2	E		ALL
6053	12		CQ		1-9	24-61-32	C00362	=B	D	*		C00348	=B	D	*	ALL
6054	12		CQ		1-6	24-61-32	C00277	=B	D			C00362	=B	D	*	ALL
6055	14		CQ		2-10	24-61-32	C00396	=B	D			C00347	=B	D		ALL
6056	12		CQ		1-7	24-61-33	C00133	=B	D	*		C01395	=B	D	*	ALL
6057	12		CQ		1-8	24-61-33	C00310	=B	D			C00196	=B	D		ALL
6058	18		CQ		1-6	24-61-33	C00161	=B	D			C00398	=B	D	*	ALL
6059	18		CQ		1-3	24-61-33	C00398	=B	D	*		C00736	=B	D		ALL
6060	18		CQ		1-8	24-61-32	C00262	=B	D			C01283	=B	D	*	YN231-YN501
6061	18		CQ		1-2	24-61-32	C01444	=B	D			C00257	=B	D		YN231-YN501
6062	10		CQ		5-9	24-61-22	C01074	=B	D			TB5060F	9	E		ALL
6063	10		CQ		2-5	24-61-22	C01399	=B	D	*		C00117	=B	D	*	YC051-YC061
6064	10		CQ		3-7	24-61-22	C01270	=B	D	*		TB5060F	10	E		ALL
6065	12		CQ		1-0	24-61-33	C01275	=B	D			C00133	=B	D	*	YC051-YD170
6065	12		CQ		1-0	24-61-33	C01275	=B	D	*		C00133	=B	D	*	YL951-YR328
6066	16		CQ		1-10	24-61-22	C00311	=B	D	*		C00195	=B	D		ALL
6067	16		CQ		1-2	24-61-22	C01356	=B	D	*		C00311	=B	D	*	ALL
6068	14		CQ		1-4	24-61-22	C00132	=B	D	*		C00583	=B	D	*	ALL
6069	12		CQ		1-9	24-61-22	C00583	=B	D	*		C00397	=B	D	*	YC051-YC061
6069	12		CQ		1-9	24-61-22	C00397	=B	D	*		C00583	=B	D	*	YC062-YR328
6070	12		CQ		2-4	24-61-22	C00397	=B	D	*		C01399	=B	D	*	YC051-YC061
6071	12		CQ		1-11	24-61-22	C00023	=B	D			C01270	=B	D	*	YC051-YC052, YC060-YC064
6071	10		CQ		4-0	24-61-22	C00023	=B	D			C01270	=B	D	*	YC053-YC059
6071	10		CQ		1-8	24-61-22	C00023	=B	D	*		C01270	=B	D	*	YC065-YL999, YR301-YR328
6071	12		CQ		1-11	24-61-22	C00023	=B	D	*		C01270	=B	D	*	YN231-YN501
6072	12		CQ		1-8	24-61-22	C03064	=B	D			C00023	=B	D		YC051-YC052, YC060-YC064
6072	12		CQ		1-8	24-61-22	C03064	=B	D			C00023	=B	D	*	YN231-YN501
6073	16		CQ		1-7	24-61-22	C00265	=B	D			C01117	=B	D		YN231-YN501
6074	12		HA		4-4	24-61-24	C00570	=B	D			TB5060D	9	E		YC051-YC059
6074	12		HA		4-4	24-61-24	TB5060D			9	E	C00570	=B	D		YC060-YD157
6074	12		HA		4-4	24-61-24	TB5060D			9	E	C00570	=B	D	*	YD158-YR328
6075	10		HA		4-9	24-61-24	C01338	=B	D			TB5060D	10	E		YC051-YC059
6075	10		HA		4-9	24-61-24	TB5060D			10	E	C01338	=B	D		YC060-YC064

WIRE LIST

D280A108

91-21-11

Section W0040

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY	Description Fam FT-IN Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W0040	286A0040	P6 (BUS SIDE) (continued)									
6075	10	HA	4-9 24-61-24	TB5060D	10	E	C01338	=B	D	*	YC065-YD157, YL951-YL999, YR301-YR328
6075	08	HA	4-9 24-61-24	TB5060D	10	E	C01338	=B	D	*	YD158-YD170
6075	10	HA	4-9 24-61-24	C01338	=B	D	TB5060D	10	E		YN231-YN501
6076	12	HA	2-0 24-61-24	C00137	=B	D	C00570	=B	D		YC051-YD157
6076	12	HA	2-0 24-61-24	C00137	=B	D	C00570	=B	D	*	YD158-YR328
6077	14	HA	2-2 24-61-24	C00312	=B	D	C00137	=B	D		YC051-YC059
6077	14	HA	2-2 24-61-24	C00137	=B	D	C00312	=B	D		YC060-YD157
6077	14	HA	2-2 24-61-24	C00137	=B	D	C00312	=B	D		YD158-YL999, YR301-YR328
6077	14	HA	2-2 24-61-24	C00312	=B	D	C00137	=B	D	*	YN231-YN501
6078	14	HA	2-1 24-61-24	C01345	=B	D	C01471	=B	D	*	ALL
6079	10	HA	1-7 24-61-24	C01271	=B	D	C01338	=B	D		YC051-YC059
6079	10	HA	1-7 24-61-24	C01338	=B	D	C01271	=B	D		YC060-YC064
6079	10	HA	1-7 24-61-24	C01338	=B	D	C01271	=B	D	*	YC065-YD157, YL951-YL999, YR301-YR328
6079	08	HA	1-7 24-61-24	C01338	=B	D	C01271	=B	D	*	YD158-YD170
6079	12	HA	1-10 24-61-24	C01338	=B	D	C01271	=B	D	*	YN231-YN501
6080	12	HA	1-3 24-61-24	C01271	=B	D	C01015	=B	D	*	YN231-YN501
6082	08	HA	4-8 24-61-24	C01366	=B	D	TB5060D	9	E		ALL
6083	08	HA	4-8 24-61-24	TB5060D	10	E	C00239	=B	D		YC051-YL954, YN231-YN235
6085	14	HA	1-3 24-61-24	C01377	=B	D	C00549	=B	D		YC051-YC059, YN501
6085	12	HA	1-3 24-61-24	C01377	=B	D	C00549	=B	D		YR301-YR328
6086	08	HA	2-3 24-61-24	C00560	=B	D	C00779	=B	D		YC051-YL954, YN231-YN235
6086	14	HA	2-6 24-61-24	C00560	=B	D	C00779	=B	D		YL955-YL999, YN236-YR328
6087	16	CQ	5-5 24-61-42	C00136	=B	D	TB5060D	3	E		ALL
6088	12	CQ	3-11 24-61-51	C00297	=B	D	TB5060C	7	E		YC051-YN236, YN501-YR316
6088	12	CQ	3-11 24-61-51	C00297	=B	D	TB5060C	7	E	*	YR317-YR328
6089	12	CQ	6-0 24-61-51	C01472	=B	D	TB5060C	7	E		YC051-YL999, YR301-YR316
6089	12	CQ	6-0 24-61-51	TB5060C	7	E	C01472	=B	D	*	YN231-YN236, YN501
6089	12	CQ	6-0 24-61-51	C01472	=B	D	TB5060C	7	E	*	YR317-YR328

WIRE LIST
D280A108

91-21-11
Section W0040
Page 8
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W0040	286A0040	P6 (BUS SIDE) (continued)													
6090	12	CQ	6-2	24-61-51	C00155	=B	D	*	TB5060C	8	E			YC051-YN236, YN501-YR316	
6090	12	CQ	6-2	24-61-51	C00155	=B	D	*	TB5060C	8	E	*		YR317-YR328	
6091	16	CQ	1-9	24-61-51	C01441	=B	D		C01346	=B	D	*		ALL	
6092	14	CQ	1-2	24-61-51	C03065	=B	D		C00155	=B	D	*		ALL	
6093	16	CQ	7-4	24-61-52	C01010	=B	D		TB5060E	10	E			ALL	
6094	16	CQ	6-10	24-61-52	C00374	=B	D		TB5060E	10	E			ALL	
6095	16	CQ	5-2	24-61-52	C01400	=B	D	*	TB5060E	11	E			ALL	
6096	12	CQ	3-1	24-61-52	TB5060E	11	E		C01290	=B	D			ALL	
6099	16	CQ	2-4	24-61-52	C00540	=B	D		C01400	=B	D	*		ALL	
6101	12	CQ	4-9	24-61-51	TB5060C	8	E		C01361	=B	D			YD158-YN236, YN501-YR316	
6101	12	CQ	4-9	24-61-51	TB5060C	8	E	*	C01361	=B	D			YR317-YR328	
6102	14	HA	2-2	24-61-24	C01015	=B	D	*	C00076	=B	D			YN231-YN501	
6104	10	CQ	6-8	24-61-22	C00117	=B	D	*	TB5060H	6	E			YC051-YC061	
6104	10	CQ	6-8	24-61-22	TB5060H	6	E		C00117	=B	D	*		YC062-YD158	
6104	10	CQ	5-0	24-61-22	TB5060F	9	E		C00117	=B	D	*		YD160-YR328	
6105	12	CQ	4-5	24-61-51	TB5060C	8	E		C00743	=B	D	*		YC051-YD157	
6106	18	CQ	8-5	24-61-61	TB5060C	2	E		C01139	=B	D			YC051-YC061	
6106	18	CQ	8-3	24-61-61	TB5060C	10	E		C01139	=B	D			YC062-YD153	
6106	18	CQ	8-3	24-61-61	TB5060C	10	E		C01139	=B	D	*		YD154-YL999, YR301-YR328	
6107	18	CQ	1-9	24-61-32	C00362	=B	D		C00306	=B	D			YC051-YD170	
6107	18	CQ	1-9	24-61-32	C00362	=B	D	*	C00306	=B	D			YL951-YR328	
6108	16	HA	1-11	24-53-11	C00788	=B	D	*	C00213	=B	D			ALL	
6112	14	HA	1-9	24-51-21	C01375	=B	D		C01008	=B	D			YC051-YC059, YD151-YD158	
6112	14	HA	1-9	24-51-24	C01375	=B	D		C01008	=B	D			YC060-YC070, YD160-YR328	
6113	10	HA	6-11	24-51-21	TB5060E	1	E		C00120	=B	D			YC051-YC059, YD151-YD157	
6113	10	HA	6-11	24-51-24	TB5060E	1	E		C00120	=B	D			YC060-YC070	
6114	14	HA	7-3	24-51-21	TB5060E	5	E		C00188	=B	D			YC051-YC059, YD151-YD157	
6114	14	HA	7-3	24-51-24	TB5060E	5	E		C00188	=B	D			YC060-YC070	
6115	14	HA	1-8	24-51-21	C00080	=B	D		C00192	=B	D			YC051-YC059	
6115	14	HA	1-8	24-51-24	C00080	=B	D		C00192	=B	D			YC060-YD153	
6115	14	HA	1-8	24-51-21	C00080	=B	D	*	C00192	=B	D			YD154-YD158	
6115	14	HA	1-8	24-51-24	C00080	=B	D	*	C00192	=B	D			YD160-YN260	

WIRE LIST

D280A108

91-21-11

Section W0040

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0040	286A0040			P6 (BUS SIDE) (continued)											
6116	14		HA		7-1	24-51-21	TB5060E	3	E		C00080	=B	D		YC051-YC059, YD151-YD153
6116	14		HA		7-1	24-51-24	TB5060E	3	E		C00080	=B	D		YC060-YC070
6116	14		HA		7-1	24-51-21	TB5060E	3	E		C00080	=B	D	*	YD154-YD157
6117	14		HA		5-1	24-51-21	C00751	=B	D		TB5060E	2	E		YC051-YC059
6117	14		HA		5-1	24-51-24	TB5060E	2	E		C00751	=B	D		YC060-YC070, YD160-YR328
6117	14		HA		5-1	24-51-21	TB5060E	2	E		C00751	=B	D		YD151-YD158
6118	14		HA		5-1	24-51-21	C01027	=B	D		TB5060E	6	E		YC051-YC059
6118	14		HA		5-1	24-51-24	TB5060E	6	E		C01027	=B	D		YC060-YC070
6118	14		HA		5-1	24-51-21	TB5060E	6	E		C01027	=B	D		YD151-YD157
6119	12		HA		4-7	24-51-21	TB5060E	6	E		C00394	=B	D		YC051-YC059, YD151-YD158
6119	12		HA		4-7	24-51-24	TB5060E	6	E		C00394	=B	D		YC060-YC070, YD160-YL954, YN231-YN235
6119	12		HA		4-7	24-51-24	TB5060E	6	N		C00394	=B	M		YL955-YL999, YN236-YR328
6120	14		HA		4-9	24-51-21	TB5060E	4	E		C00392	=B	D		YC051-YC059, YD151-YD158
6120	14		HA		4-9	24-51-24	TB5060E	4	E		C00392	=B	D		YC060-YC070, YD160-YL954, YN231-YN235
6120	14		HA		4-9	24-51-24	TB5060E	4	N		C00392	=B	M		YL955-YL999, YN236-YR328
6121	14		HA		4-9	24-51-21	TB5060E	2	E		C00395	=B	D		YC051-YC059, YD151-YD158
6121	14		HA		4-9	24-51-24	TB5060E	2	E		C00395	=B	D		YC060-YC070
6122	14		HA		2-10	24-51-21	C01076	=B	D		C01037	=B	D		YC051-YC059, YD151-YD158
6122	14		HA		2-10	24-51-24	C01076	=B	D		C01037	=B	D		YC060-YC070, YD160-YR328
6123	14		HA		1-5	24-51-21	C01042	=B	D		C01315	=B	D		YC051-YC059, YD151-YD158
6123	14		HA		1-5	24-51-24	C01042	=B	D		C01315	=B	D		YC060-YC070, YD160-YR328
6124	18		CQ		1-6	24-61-33	C00361	=B	D		C01275	=B	D	*	YC051-YD170
6124	18		CQ		1-6	24-61-33	C00361	=B	D		C01275	=B	D		YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0040

Page 10

Nov 12/2012

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0040	286A0040			P6 (BUS SIDE) (continued)											
6125	08		HA		6-3	24-51-21	TB5060E		1	E		C00787	=B	D	YC051-YC059, YD151-YD158
6125	08		HA		6-3	24-51-24	TB5060E		1	E		C00787	=B	D	YC060-YC070, YD160-YR328
6126	10		HA		1-1	24-51-21	C00786		=B	D	*	C00841	B1	D	YC051-YC059, YD151-YD158
6126	10		HA		1-1	24-51-24	C00786		=B	D	*	C00841	B1	D	YC060-YC070, YD160-YR328
6127	10		CQ		1-8	24-61-22	C00211		=B	D		C01068	=B	D	ALL
6128	14		HA		2-1	24-51-21	C00388		=B	D		C00840	C1	D	YC051-YC059, YD151-YD158
6128	14		HA		2-1	24-51-24	C00388		=B	D		C00840	C1	D	YC060-YC070, YD160-YR328
6129	08		HA		5-8	24-51-21	TB5060E		5	E		C00841	C1	D	YC051-YC059, YD151-YD158
6129	08		HA		5-8	24-51-24	TB5060E		5	E		C00841	C1	D	YC060-YC070, YD160-YR328
6130	14		HA		3-9	24-51-21	TB5060E		2	E		C02043	=B	D	YC051-YC059, YD151-YD153
6130	14		HA		3-9	24-51-24	TB5060E		2	E		C02043	=B	D	YC060-YC070
6130	14		HA		3-9	24-51-21	TB5060E		2	E		C02043	=B	D	YD154-YD158
6130	14		HA		3-9	24-51-24	TB5060E		2	E		C02043	=B	D	YD160-YR328
6132	14		CQ		3-6	24-51-21	C01467		=B	D		TB5060E	6	E	YC051-YC059
6132	14		HA		3-6	24-51-24	TB5060E		6	E		C01467	=B	D	YC060-YC070, YD160-YR328
6132	14		HA		3-6	24-51-21	TB5060E		6	E		C01467	=B	D	YD151-YD158
6133	14		HA		4-2	24-51-21	TB5060E		4	E		C00400	=B	D	YC051-YC059
6133	14		HA		4-2	24-51-24	TB5060E		4	E		C00400	=B	D	YC060-YR323, YR325-YR328
6134	12		HA		3-6	24-51-21	TB5060E		7	E		C00884	A2	D	YC051-YC059, YD151-YD157
6134	12		HA		3-6	24-51-22	TB5060E		7	E		C00884	A2	D	YC060-YC070, YL951-YR328
6134	10		HA		3-3	24-51-21	TB5060E		7	E		C00884	A2	D	YD158
6135	12		HA		3-5	24-51-21	TB5060E		8	E		C00884	B2	D	YC051-YC059, YD151-YD157
6135	12		HA		3-5	24-51-22	TB5060E		8	E		C00884	B2	D	YC060-YC070, YL951-YR328
6135	10		HA		3-2	24-51-21	TB5060E		8	E		C00884	B2	D	YD158

WIRE LIST

D280A108

91-21-11

Section W0040

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0040	286A0040			P6 (BUS SIDE) (continued)											
6136	12	HA			3-4	24-51-21	TB5060E	9	E		C00884	C2	D		YC051-YC059, YD151-YD157
6136	12	HA			3-4	24-51-22	TB5060E	9	E		C00884	C2	D		YC060-YC070, YL951-YR328
6136	10	HA			3-1	24-51-21	TB5060E	9	E		C00884	C2	D	*	YD158
6144	14	HA			7-5	24-51-21	TB5060E	5	E		C00857	C1	D	*	YD158
6144	14	HA			7-5	24-51-24	TB5060E	5	E		C00857	C1	D	*	YD160-YR328
6145	14	HA			7-7	24-51-21	TB5060E	3	E		C00857	B1	D	*	YD158
6145	14	HA			7-7	24-51-24	TB5060E	3	E		C00857	B1	D	*	YD160-YR328
6146	10	HA			7-4	24-51-21	TB5060E	1	E		C00857	A1	D	*	YD158
6146	10	HA			7-4	24-51-24	TB5060E	1	E		C00857	A1	D	*	YD160-YR328
6147	10	HA			1-7	24-51-21	C00857	A1	D	*	C00120	=B	D		YD158
6147	10	HA			1-7	24-51-24	C00857	A1	D	*	C00120	=B	D		YD160-YR328
6148	14	HA			1-8	24-51-21	C00857	B1	D	*	C00080	=B	D	*	YD158
6148	14	HA			1-8	24-51-24	C00857	B1	D	*	C00080	=B	D	*	YD160-YN260
6149	14	HA			1-10	24-51-21	C00857	C1	D	*	C00188	=B	D		YD158
6149	14	HA			1-10	24-51-24	C00857	C1	D	*	C00188	=B	D		YD160-YR328
6154	08	HA			6-1	24-51-21	TB5060E	3	E		C00786	=B	D	*	YC051-YC059, YD151-YD158
6154	08	HA			6-1	24-51-24	TB5060E	3	E		C00786	=B	D	*	YC060-YC070, YD160-YR328
6155	16	CQ			2-1	24-61-52	C01466	=B	D		C00033	=B	D		ALL
6156	08	HA			1-3	24-51-21	C00787	=B	D		C00841	A1	D		YC051-YC059, YD151-YD158
6156	08	HA			1-3	24-51-24	C00787	=B	D		C00841	A1	D		YC060-YC070, YD160-YR328
6160	14	HA			3-0	24-61-24	C01515	=B	D		C01628	=B	D		YC051-YC059, YC065-YD153
6160	14	HA			3-0	24-61-24	C01515	=B	D		C01628	=B	D	*	YC060-YC064
6160	14	HA			2-2	24-61-24	C01515	=B	D	*	C01628	=B	D		YD154-YD155
6161	14	HA			1-9	24-61-24	C01116	=B	D		C01634	=B	D	*	YD158-YD170
6163	14	HA			1-6	24-51-21	C00077	=B	D	*	C01162	=B	D		YC051-YC059
6163	14	HA			1-6	24-51-24	C01162	=B	D		C00077	=B	D	*	YC060-YC070
6163	14	HA			1-6	24-51-21	C01162	=B	D		C00077	=B	D	*	YD151-YD153
6163	14	HA			1-6	24-51-21	C01162	=B	D	*	C00077	=B	D	*	YD154-YD158
6163	14	HA			1-6	24-51-24	C01162	=B	D	*	C00077	=B	D	*	YD160-YL999, YR301-YR328
6165	14	HA			2-1	24-61-24	C01634	=B	D	*	C01161	=B	D		YD158-YD170
6176	16	CQ			6-11	24-61-22	TB5060F	10	E		C01500	=B	D		YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0040

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0040		286A0040				P6 (BUS SIDE) (continued)									
	6182	16	CQ		0-11	24-61-22	C01399	=B	D		C01495	=B	D		YC051-YC061
	6188	14	CQ		1-5	24-51-11	C01101	=B	D		C01452	=B	D		YC051-YC059
	6188	14	GA		1-5	24-51-11	C01452	=B	D		C01101	=B	D		YC060-YD153
	6188	14	CQ		1-5	24-51-11	C01452	=B	D		C01101	=B	D		YD154-YD157
	6189	14	HA		2-0	24-61-24	C01630	=B	D		C01628	=B	D		YD157-YL952, YN231-YN232
	6189	14	HA		2-0	24-61-24	C01630	=B	D		C01628	=B	D	*	YL953-YL999, YN233-YR328
	6194	12	CQ		1-5	24-61-51	C00743	=B	D	*	C01361	=B	D		YC051-YD157
	6195	14	HA		2-0	24-51-21	C00884	A2	D	*	C01633	A2	D		YD158
	6196	14	HA		1-10	24-51-21	C00884	B2	D	*	C01633	B2	D		YD158-YD170
	6197	14	HA		1-9	24-51-21	C00884	C2	D	*	C01633	C2	D		YD158-YD170
	6198	12	CQ		4-6	24-61-33	C01395	=B	D	*	TB5060D	6	E		ALL
	6202	20	HA		3-10	24-53-11	T00052	HV	E		C02043	=L	D		ALL
	6203	10	HA		4-4	24-53-11	T00052	LV1	E		TB5060B	2	E		ALL
	6204	08	HA		1-7	24-53-11	T00052	G	E		GD00634	AC..	E		ALL
	6205	22	CQ		4-1	24-53-11	T00391	HV	E		C02047	=L	D		ALL
	6206	12	CQ		3-2	24-53-11	T00391	LV	E		TB5060D	4	E		ALL
	6207	10	CQ		1-0	24-53-11	T00391	G	E		GD00636	AC..	E		ALL
	6208	16	CQ		1-6	24-61-42	C01284	=B	D		C00136	=B	D	*	ALL
	6209	18	CQ		1-3	24-61-32	C00026	=B	D		C01283	=B	D		YC051-YL999, YR301-YR328
	6209	18	CQ		1-3	24-61-32	C00026	=B	D		C01283	=B	D	*	YN231-YN501
	6210	12	CQ		3-1	24-54-11	D11712A	5			TB5060C	6	E		ALL
	6212	10	CQ		2-11	24-61-41	D11712B	A4			TB5060C	3	E		ALL
	6213	12	CQ		3-2	24-61-31	D11712A	4			TB5060C	4	E		ALL
	6214	12	CQ		2-8	24-61-32	D11712A	8			TB5060D	1	E		ALL
	6215	10	CQ		2-3	24-61-42	D11712B	A1			TB5060D	3	E		ALL
	6216	10	CQ		2-9	24-61-52	D11714A	A1			TB5060E	10	E		ALL
	6217	10	CQ		3-7	24-61-52	D11714A	A4			TB5060C	1	E		ALL
	6218	12	CQ		3-7	24-61-51	D11714A	A3			TB5060C	7	E		YC051-YR316
	6218	12	CQ		3-7	24-61-51	D11714A	A3			TB5060C	7	E	*1	YR317-YR328
	6219	12	CQ		2-4	24-61-33	D11712A	7			TB5060D	6	E		ALL
	6238	14	CQ		6-3	24-51-14	TB5060F	2	E		C01650	=B	D		YD160-YR328
	6239	14	HA		4-9	24-51-24	TB5060E	2	E		C01649	=B	D		YD160-YR328
	6247	14	HA		1-2	24-61-24	C01464	=B	D		C01313	=B	D		YC051-YD155
	6247	12	HA		1-2	24-61-24	C01464	=B	D		C01313	=B	D		YD157-YR328
	6249	14	CQ		7-0	24-51-11	TB5060F	2	E		C01483	=B	D		YD158
	6249	14	CQ		7-0	24-51-14	TB5060F	2	E		C01483	=B	D		YD160-YR328

WIRE LIST

D280A108

91-21-11

Section W0040

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0040	286A0040				P6 (BUS SIDE) (continued)										
6253	10	HA			1-4	24-61-24	C01360	=B	D		C00166	=B	D		YN501-YR328
6299	18	CQ			1-1	24-61-32	C00082	=B	D	*	C01583	=B	D		YC060-YR328
6313	14	HA			1-3	24-61-24	C00549	=B	D		C01584	=B	D		YC060-YN260
6320	14	HA			7-7	24-51-21	TB5060E		3	E	C00192	=B	D		YC051-YC052
6325	10	CQ			2-5	24-61-22	C00117	=B	D	*	C01495	=B	D	*	YC062-YD170
6326	12	CQ			2-4	24-61-22	C01495	=B	D	*	C00397	=B	D	*	YC062-YD157
6327	18	CQ			6-5	24-61-61	TB5060C		10	E	C01399	=B	D		YC062-YN236, YN501-YR316
6327	18	CQ			6-5	24-61-61	TB5060C		10	E	C01399	=B	D		YR317-YR328
6339	14	CQ			1-7	24-51-15	C01451	=B	D		C01670	=B	D		YL951-YL967, YN231-YN235
6340	14	HA			2-2	24-51-24	C00857	B1	D	*	C00192	=B	D		YN501-YR328
6345	12	CQ			4-0	24-61-22	C00023	=B	D		C01613	=B	D		YC053-YC059
6345	12	CQ			2-2	24-61-22	C00023	=B	D	*	C01613	=B	D	*	YC065-YL999, YR301-YR328
6346	12	CQ			4-0	24-61-22	C01613	=B	D		C03064	=B	D		YC053-YC059
6346	12	CQ			1-7	24-61-22	C01613	=B	D	*	C03064	=B	D		YC065-YL999, YR301-YR328
6347	12	HA			4-0	24-61-24	C01023	=B	D		C01614	=B	D		YC053-YC059
6347	12	HA			2-5	24-61-24	C01023	=B	D	*	C01614	=B	D	*	YC065-YD157, YL951-YL999, YR301-YR328
6347	10	HA			2-2	24-61-24	C01023	=B	D	*	C01614	=B	D	*	YD158-YD170
6348	12	HA			4-0	24-61-24	C01614	=B	D		C00076	=B	D		YC053-YC059
6348	12	HA			1-3	24-61-24	C01614	=B	D	*	C00076	=B	D		YC065-YL999, YR301-YR328
6354	14	CQ			6-0	24-51-11	TB5060K		1	E	C01456	=B	D		YC051-YC059
6354	14	CQ			6-0	24-51-15	C01456	=B	D		TB5060K		1	E	YC060-YC070
6354	14	CQ			6-0	24-51-11	C01456	=B	D		TB5060K		1	E	YD151-YD157
6354	14	CQ			4-3	24-51-11	TB5060K		1	E	C01456	=B	D		YD158
6354	14	CQ			4-4	24-51-15	TB5060K		1	E	C01456	=B	D		YD160-YR328
6355	12	CQ			6-0	24-51-11	TB5060K		3	E	C01453	=B	D		YC051-YC059
6355	12	CQ			6-0	24-51-15	TB5060K		3	E	C01453	=B	D		YC060-YD157
6355	14	CQ			4-7	24-51-11	TB5060K		3	E	C01453	=B	D		YD158
6355	14	CQ			4-7	24-51-15	TB5060K		3	E	C01453	=B	D		YD160-YR306
6355	12	CQ			4-7	24-51-15	TB5060K		3	E	C01453	=B	D		YR307-YR328
6356	14	CQ			6-0	24-51-11	TB5060K		5	E	C01455	=B	D		YC051-YC059
6356	14	CQ			6-0	24-51-15	TB5060K		5	E	C01455	=B	D		YC060-YD157
6356	14	CQ			4-6	24-51-11	TB5060K		5	E	C01455	=B	D		YD158

WIRE LIST

D280A108

91-21-11

Section W0040

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To				Effectivity	
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W0040	286A0040			P6 (BUS SIDE) (continued)												
6356	14		CQ	4-7	24-51-15	TB5060K	5	E		C01455	=B	D		YD160-YR328		
6392	18		CQ	8-6	24-61-61	TB5060C	10	E		C01627	=B	D		YN231-YN501		
6393	18		CQ	4-0	24-61-61	C01139	=B	D		C01627	=B	D		YC051-YD153		
6393	18		CQ	4-0	24-61-61	C01139	=B	D	*	C01627	=B	D		YD154-YD157		
6393	18		CQ	2-5	24-61-61	C01139	=B	D	*	C01627	=B	D		YD158-YL999, YR301-YR328		
6397	10		CQ	2-3	24-61-22	C00117	=B	D	*	C01637	=B	D	*	YL951-YR328		
6398	10		CQ	0-10	24-61-22	C01495	=B	D	*	C01637	=B	D	*	YD158-YD170		
6399	12		CQ	2-2	24-61-22	C01637	=B	D	*	C00397	=B	D	*	YD158-YR328		
6400	14		HA	1-6	24-61-24	C01401	=B	D		C01638	=B	D	*	YD158-YR328		
6401	14		HA	1-2	24-61-24	C01638	=B	D	*	C01471	=B	D	*	YD158-YR328		
6402	14		CQ	5-2	24-51-11	TB5060F	5	E		C01639	=B	D		YD158		
6403	14		HA	4-7	24-51-21	TB5060E	6	E		C01640	=B	D	*	YD158		
6404	14		HA	1-11	24-51-21	C01640	=B	D	*	C01027	=B	D		YD158		
6404	14		HA	1-11	24-51-24	C01658	=B	D	*	C01027	=B	D		YD160-YR328		
6423	14		CQ	7-5	24-51-15	TB5060K	2	E		C01643	=B	D		YL951-YL999, YN232-YR328		
6424	14		CQ	7-7	24-51-15	C01641	=B	D		TB5060K	6	E		YL951-YR328		
6426	16		CQ	1-2	24-61-22	C00566	=B	D		C01662	=B	D		YL953-YL999, YR301-YR328		
6430	14		HA	1-2	24-61-24	C01631	=B	D		C01663	=B	D		YL953-YL999, YR301-YR328		
6437	14		CQ	5-2	24-51-14	TB5060F	5	E		C01659	=B	D		YD160-YR328		
6438	14		HA	4-7	24-51-24	TB5060E	6	E		C01658	=B	D	*	YD160-YR328		
6497	14		HA	2-5	24-61-24	C01628	=B	D	*	C01698	=B	D		YC060-YC064		
6497	14		HA	1-4	24-61-24	C01628	=B	D	*	C01698	=B	D		YL953-YL999, YN233-YR328		
6499	08		HA	4-2	24-61-24	TB5060D	10	E		C00207	=B	D	*	YL955-YL999, YN236-YR328		
6500	10		HA	1-0	24-61-24	C00204	=B	D		C00207	=B	D	*	YL955-YL999, YN236-YR328		
6501	14		HA	1-2	24-61-24	C00239	=B	D		C00560	=B	D	*	YL955-YL999, YN236-YR328		
6503	08		HA	1-3	24-61-24	C01364	=B	D		C01360	=B	D		YL955-YL999, YN236-YR328		
6513	18		CQ	4-10	24-61-61	TB5060C	9	E		C01936	=B	D		YN501-YR316		
6513	18		CQ	4-10	24-61-61	TB5060C	9	E	*	C01936	=B	D		YR317-YR328		
6514	14		CQ	1-8	24-51-15	C01945	=B	D		C01452	=B	D		YN501		
6514	14		CQ	1-8	24-51-15	C01452	=B	D		C01945	=B	D		YR301-YR328		

WIRE LIST

D280A108

91-21-11

Section W0040

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0040	286A0040				P6 (BUS SIDE) (continued)											
6515	18		CQ		8-6	24-61-51		C01949	=B	D		TB5060C	7	E		YN501
6515	18		CQ		8-6	24-61-51		TB5060C		7	E		C01949	=B	D	YR301-YR316
6515	18		CQ		8-6	24-61-51		TB5060C		7	E	*1	C01949	=B	D	YR317-YR328
6517	14		CQ		2-0	24-61-24		C01338	=B	D		C01272	=B	D		YC065
6517	14		CQ		1-8	24-61-24		C01338	=B	D		C01272	=B	D		YL964-YL999
6517	14		CQ		1-9	24-61-24		C01338	=B	D		C01272	=B	D		YN236-YR328
ZZAA	02		ZB		0-0	24-51-14		C00399	=B	D		C00267	=B	D		YN231-YN501
ZZAB	02		ZB		0-0	24-51-14		C00268	=B	D		C00344	=B	D		YN231-YN501
ZZAE	03		ZB		0-0	24-51-21		C01383	=B	D		C01379	=B	D		YC051-YC059, YD151-YD158
ZZAE	03		ZB		0-0	24-51-24		C01383	=B	D		C01379	=B	D		YC060-YC070, YD160-YR328
ZZAF	00		ZB		0-0	24-51-21		C01385	=B	D		C01379	=B	D		YC051-YC059, YD151-YD158
ZZAF	00		ZB		0-0	24-51-24		C01385	=B	D		C01379	=B	D		YC060-YC070, YD160-YR328
ZZAG	00		ZB		0-0	24-51-21		C01383	=B	D		C01385	=B	D		YC051-YC059, YD151-YD158
ZZAG	00		ZB		0-0	24-51-24		C01383	=B	D		C01385	=B	D		YC060-YC070, YD160-YR328
ZZAH	02		ZB		0-0	24-51-21		C01037	=B	D		C01042	=B	D		YC051-YC059, YD151-YD158
ZZAH	02		ZB		0-0	24-51-24		C01037	=B	D		C01042	=B	D		YC060-YC070, YD160-YR328
ZZAJ	02		ZB		0-0	24-53-11		C00213	=B	D		C01443	=B	D		ALL
ZZAL	02		ZB		0-0	24-53-11		C00219	=B	D		C00284	=B	D		ALL
ZZAM	04		ZB		0-0	24-53-11		C00355	=B	D		C00309	=B	D		ALL
ZZAN	00		ZB		0-0	24-53-11		C00355	=B	D		C00283	=B	D		ALL
ZZAO	00		ZB		0-0	24-53-11		C00283	=B	D		C00308	=B	D		ALL
ZZAP	00		ZB		0-0	24-51-11		C01255	=B	D		C01216	=B	D		YC051-YD153
ZZAQ	02		ZB		0-0	24-51-21		C01239	=B	D		C01262	=B	D		YC051-YC059, YD151-YD158
ZZAQ	02		ZB		0-0	24-51-24		C01239	=B	D		C01262	=B	D		YC060-YC070, YD160-YD170, YL955-YL999, YN236-YR328
ZZAQ	00		ZB		0-0	24-51-24		C01239	=B	D		C01262	=B	D		YL951-YL954, YN231-YN235
ZZAR	00		ZB		0-0	24-53-11		C00308	=B	D		C00309	=B	D		ALL

WIRE LIST

D280A108

91-21-11

Section W0040

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0040		286A0040			P6 (BUS SIDE) (continued)											
ZZAT		02		ZB		0-0	24-61-32	C00347	=B	D		C00348	=B	D		ALL
ZZAV		05		ZB		0-0	24-61-32	C00277	=B	D		C01047	=B	D		ALL
ZZAW		00		ZB		0-0	24-61-32	C01413	=B	D		C00277	=B	D		ALL
ZZAX		00		ZB		0-0	24-61-32	C01267	=B	D		C01413	=B	D		ALL
ZZAY		00		ZB		0-0	24-61-32	C00154	=B	D		C01267	=B	D		ALL
ZZAZ		00		ZB		0-0	24-61-32	C01047	=B	D		C00154	=B	D		ALL
ZZBA		04		ZB		0-0	24-61-32	C00396	=B	D		C00405	=B	D		ALL
ZZBB		00		ZB		0-0	24-61-32	C00407	=B	D		C00396	=B	D		ALL
ZZBC		00		ZB		0-0	24-61-32	C00403	=B	D		C00407	=B	D		ALL
ZZBD		00		ZB		0-0	24-61-32	C00405	=B	D		C00403	=B	D		ALL
ZZBE		04		ZB		0-0	24-61-33	C01395	=B	D		C01321	=B	D		ALL
ZZBF		00		ZB		0-0	24-61-33	C01395	=B	D		C01320	=B	D		ALL
ZZBG		00		ZB		0-0	24-61-33	C01320	=B	D		C01396	=B	D		ALL
ZZBH		00		ZB		0-0	24-61-33	C01396	=B	D		C01321	=B	D		ALL
ZZBI		02		ZB		0-0	24-61-33	C00133	=B	D		C00310	=B	D		ALL
ZZBJ		05		ZB		0-0	24-61-33	C01275	=B	D		C01355	=B	D		ALL
ZZBK		00		ZB		0-0	24-61-33	C01276	=B	D		C01275	=B	D		ALL
ZZBL		00		ZB		0-0	24-61-33	C01277	=B	D		C01276	=B	D		ALL
ZZBM		00		ZB		0-0	24-61-33	C01278	=B	D		C01277	=B	D		ALL
ZZBN		00		ZB		0-0	24-61-33	C01355	=B	D		C01278	=B	D		ALL
ZZBP		02		ZB		0-0	24-61-33	C00161	=B	D		C00282	=B	D		ALL
ZZBQ		05		ZB		0-0	24-61-32	C01269	=B	D		C01283	=B	D		YC051-YC064, YC067-YL963, YN231-YN235
ZZBQ		03		ZB		0-0	24-61-32	C01286	=B	D		C01283	=B	D		YC065, YL964-YL999, YN236-YR328
ZZBR		00		ZB		0-0	24-61-32	C01272	=B	D		C01269	=B	D		YC051-YC064, YC067-YL963, YN231-YN235
ZZBS		00		ZB		0-0	24-61-32	C01286	=B	D		C01272	=B	D		YC051-YC064, YC067-YL963, YN231-YN235
ZZBT		00		ZB		0-0	24-61-32	C01287	=B	D		C01286	=B	D		ALL
ZZBU		00		ZB		0-0	24-61-32	C01283	=B	D		C01287	=B	D		ALL
ZZBW		02		ZB		0-0	24-61-52	C01285	=B	D		C01290	=B	D		ALL
ZZCA		03		ZB		0-0	24-61-32	C00262	=B	D		C00257	=B	D		YN231-YN501
ZZCB		00		ZB		0-0	24-61-32	C00262	=B	D		C00263	=B	D		YC051-YL999, YR301-YR328
ZZCB		00		ZB		0-0	24-61-32	C00263	=B	D		C00262	=B	D		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W0040

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0040	286A0040			P6 (BUS SIDE) (continued)											
ZZCC	00		ZB		0-0	24-61-32	C00257	=B	D		C00263	=B	D		YN231-YN501
ZZCD	04		ZB		0-0	24-61-22	C01074	=B	D		C00781	=B	D		ALL
ZZCE	00		ZB		0-0	24-61-22	C01068	=B	D		C01074	=B	D		ALL
ZZCF	00		ZB		0-0	24-61-22	C00799	=B	D		C01068	=B	D		ALL
ZZCG	00		ZB		0-0	24-61-22	C00781	=B	D		C00799	=B	D		ALL
ZZCH	03		ZB		0-0	24-61-22	C01081	=B	D		C00780	=B	D		ALL
ZZCI	00		ZB		0-0	24-61-22	C01085	=B	D		C01081	=B	D		ALL
ZZCJ	00		ZB		0-0	24-61-22	C00780	=B	D		C01085	=B	D		ALL
ZZCK	03		ZB		0-0	24-61-22	C00211	=B	D		C00566	=B	D		ALL
ZZCL	00		ZB		0-0	24-61-22	C00210	=B	D		C00211	=B	D		ALL
ZZCM	00		ZB		0-0	24-61-22	C00566	=B	D		C00210	=B	D		ALL
ZZCN	00		ZB		0-0	24-61-22	C00265	=B	D		C00796	=B	D		YN231-YN501
ZZCO	02		ZB		0-0	24-61-24	C00312	=B	D		C01401	=B	D		ALL
ZZCP	02		ZB		0-0	24-61-24	C00124	=B	D		C00076	=B	D		YN231-YN501
ZZCQ	00		ZB		0-0	24-61-24	C00797	=B	D		C00266	=B	D		YN231-YN501
ZZCR	06		ZB		0-0	24-61-24	C01364	=B	D		C01263	=B	D		ALL
ZZCS	00		ZB		0-0	24-61-24	C01366	=B	D		C01364	=B	D		ALL
ZZCT	00		ZB		0-0	24-61-24	C01373	=B	D		C01366	=B	D		ALL
ZZCU	00		ZB		0-0	24-61-24	C01370	=B	D		C01373	=B	D		ALL
ZZCV	00		ZB		0-0	24-61-24	C01194	=B	D		C01370	=B	D		ALL
ZZCW	00		ZB		0-0	24-61-24	C01263	=B	D		C01194	=B	D		ALL
ZZCX	03		ZB		0-0	24-61-24	C00549	=B	D		C01206	=B	D		ALL
ZZCY	00		ZB		0-0	24-61-24	C00549	=B	D		C01393	=B	D		ALL
ZZCZ	00		ZB		0-0	24-61-24	C01393	=B	D		C01206	=B	D		ALL
ZZDA	04		ZB		0-0	24-61-24	C00779	=B	D		C00204	=B	D		ALL
ZZDB	00		ZB		0-0	24-61-24	C00779	=B	D		C01070	=B	D		ALL
ZZDC	00		ZB		0-0	24-61-24	C01070	=B	D		C00363	=B	D		ALL
ZZDD	00		ZB		0-0	24-61-24	C00363	=B	D		C00204	=B	D		ALL
ZZDE	00		ZB		0-0	24-61-24	C00207	=B	D		C00440	=B	D		ALL
ZZDF	03		ZB		0-0	24-61-24	C00207	=B	D		C01464	=B	D		ALL
ZZDG	02		ZB		0-0	24-61-32	C01319	=B	D		C01318	=B	D		ALL
ZZDH	04		ZB		0-0	24-61-24	C01064	=B	D		C01313	=B	D		ALL
ZZDI	00		ZB		0-0	24-61-24	C01313	=B	D		C00716	=B	D		ALL
ZZDJ	00		ZB		0-0	24-61-24	C00716	=B	D		C01046	=B	D		ALL
ZZDK	00		ZB		0-0	24-61-24	C01046	=B	D		C01064	=B	D		ALL
ZZDL	03		ZB		0-0	24-61-51	C01441	=B	D		C00737	=B	D		ALL
ZZDM	00		ZB		0-0	24-61-51	C00032	=B	D		C01441	=B	D		ALL
ZZDN	00		ZB		0-0	24-61-51	C00737	=B	D		C00032	=B	D		ALL
ZZDO	03		ZB		0-0	24-61-51	C01328	=B	D		C01397	=B	D		ALL

WIRE LIST

D280A108

91-21-11

Section W0040

Page 18

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0040		286A0040			P6 (BUS SIDE) (continued)											
ZZDQ		05		ZB		0-0	24-61-51	C00297	=B	D		C01021	=B	D		ALL
ZZDR		00		ZB		0-0	24-61-51	C00452	=B	D		C00297	=B	D		ALL
ZZDS		00		ZB		0-0	24-61-51	C00296	=B	D		C00452	=B	D		ALL
ZZDT		00		ZB		0-0	24-61-51	C01022	=B	D		C00296	=B	D		ALL
ZZDU		00		ZB		0-0	24-61-51	C01021	=B	D		C01022	=B	D		ALL
ZZDV		02		ZB		0-0	24-51-21	C00151	=B	D		C01391	=B	D		YC051-YC059, YD151-YD158
ZZDV		02		ZB		0-0	24-51-24	C00151	=B	D		C01391	=B	D		YC060-YC070, YD160-YR328
ZZDW		02		ZB		0-0	24-51-24	C00345	=B	D		C00258	=B	D		YN231-YN501
ZZDX		02		ZB		0-0	24-54-11	C00072	=B	D		C02047	=B	D		ALL
ZZEA		02		ZB		0-0	24-61-24	C01004	=B	D		C01447	=B	D		ALL
ZZEB		02		ZB		0-0	24-61-51	C01361	=B	D		C01362	=B	D		ALL
ZZEC		03		ZB		0-0	24-61-24	C01469	=B	D		C00266	=B	D		YN231-YN501
ZZED		03		ZB		0-0	24-61-22	C01470	=B	D		C00265	=B	D		YN231-YN501
ZZEE		07		ZB		0-0	24-61-32	C01169	=B	D		C01176	=B	D		YC051-YL999, YR301-YR328
ZZEF		00		ZB		0-0	24-61-51	C03065	=B	D		C01397	=B	D		ALL
ZZEG		00		ZB		0-0	24-61-51	C01328	=B	D		C03065	=B	D		ALL
ZZEH		00		ZB		0-0	24-61-32	C01164	=B	D		C00263	=B	D		YC051-YL999, YR301-YR328
ZZEI		00		ZB		0-0	24-61-32	C00262	=B	D		C01177	=B	D		YC051-YL999, YR301-YR328
ZZEJ		00		ZB		0-0	24-61-32	C01177	=B	D		C01176	=B	D		YC051-YL999, YR301-YR328
ZZEK		04		ZB		0-0	24-61-24	C01469	=B	D		C01161	=B	D		YC051-YL999, YR301-YR328
ZZEL		00		ZB		0-0	24-61-24	C00797	=B	D		C01178	=B	D		YC051-YL999, YR301-YR328
ZZEM		02		ZB		0-0	24-61-24	C01172	=B	D		C00076	=B	D		YC051-YL999, YR301-YR328
ZZEN		00		ZB		0-0	24-61-24	C01178	=B	D		C01161	=B	D		YC051-YL999, YR301-YR328
ZZEO		02		ZB		0-0	24-51-21	C01480	=B	D		C01375	=B	D		YC051-YC059
ZZEO		02		ZB		0-0	24-51-24	C01375	=B	D		C01480	=B	D		YC060-YC070, YD160-YR328
ZZEO		02		ZB		0-0	24-51-21	C01375	=B	D		C01480	=B	D		YD151-YD158
ZZEP		00		ZB		0-0	24-61-22	C00796	=B	D		C00555	=B	D		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W0040

Page 19

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0040	286A0040			P6 (BUS SIDE) (continued)											
ZZEQ	00		ZB		0-0	24-61-22	C00555	= B	D		C01158	= B	D		YC051-YL999, YR301-YR328
ZZER	00		ZB		0-0	24-61-24	C00440	= B	D		C01464	= B	D		ALL
ZZEU	04		ZB		0-0	24-61-22	C01470	= B	D		C01158	= B	D		YC051-YL999, YR301-YR328
ZZFA	00		ZB		0-0	24-61-22	C01470	= B	D		C00796	= B	D		ALL
ZZFB	00		ZB		0-0	24-61-24	C01469	= B	D		C00797	= B	D		ALL
ZZFC	02		ZB		0-0	24-51-11	C01452	= B	D		C01453	= B	D		YC051-YC059
ZZFC	02		ZB		0-0	24-51-15	C01453	= B	D		C01452	= B	D		YC060-YD153, YD160-YR328
ZZFC	02		ZB		0-0	24-51-11	C01453	= B	D		C01452	= B	D		YD154-YD158
ZZFD	02		ZB		0-0	24-51-11	C01455	= B	D		C01454	= B	D		YC051-YC059, YD154-YD158
ZZFD	02		ZB		0-0	24-51-15	C01455	= B	D		C01454	= B	D		YC060-YD153, YD160-YR328
ZZFE	02		ZB		0-0	24-51-11	C01451	= B	D		C01456	= B	D		YC051-YC059
ZZFE	02		ZB		0-0	24-51-15	C01456	= B	D		C01451	= B	D		YC060-YD153, YD160-YN260
ZZFE	02		ZB		0-0	24-51-11	C01456	= B	D		C01451	= B	D		YD154-YD158
ZZFF	00		ZB		0-0	24-61-32	C01169	= B	D		C01166	= B	D		YC051-YL999, YR301-YR328
ZZFG	00		ZB		0-0	24-61-32	C01166	= B	D		C01164	= B	D		YC051-YL999, YR301-YR328
ZZFI	03		ZB		0-0	24-51-11	C00744	= B	D		C01216	= B	D		YC051-YC059, YD151-YD157
ZZFI	03		ZB		0-0	24-51-14	C00744	= B	D		C01216	= B	D		YC060-YC070
ZZFJ	00		ZB		0-0	24-51-11	C00744	= B	D		C01255	= B	D		YC051-YC059, YD151-YD157
ZZFJ	00		ZB		0-0	24-51-14	C00744	= B	D		C01255	= B	D		YC060-YC070
ZZFK	00		ZB		0-0	24-51-11	C01255	= B	D		C01216	= B	D		YD154-YD157
ZZFM	02		ZB		0-0	24-61-24	C01468	= B	D		C01611	= B	D		YN231-YN501
ZZGB	00		ZB		0-0	24-51-24	C01262	= B	D		C01694	= B	D		YL951-YL954, YN231-YN235
ZZGC	03		ZB		0-0	24-51-24	C01694	= B	D		C01239	= B	D		YL951-YL954, YN231-YN235
ZZQA	02		ZK		0-0	24-61-32	TB5060D	1	E		TB5060D	2	E		ALL
ZZQB	02		ZK		0-0	24-54-11	TB5060C	5	E		TB5060C	6	E		ALL
ZZQD	02		ZK		0-0	24-53-11	TB5060B	2	E		TB5060B	3	E		ALL
ZZQE	02		ZK		0-0	24-61-51	TB5060C	7	E		TB5060C	8	E		ALL

WIRE LIST

D280A108

91-21-11

Section W0040

Page 20

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0040	286A0040			P6 (BUS SIDE) (continued)											
ZZQG	02		ZK		0-0	24-51-11	TB5060F	1	E		TB5060F	2	E		YC051-YC059, YD151-YD158
ZZQG	02		ZK		0-0	24-51-14	TB5060F	1	E		TB5060F	2	E		YC060-YC070, YD160-YR328
ZZQH	02		ZK		0-0	24-51-11	TB5060F	3	E		TB5060F	4	E		YC051-YC059, YD151-YD158
ZZQH	02		ZK		0-0	24-51-14	TB5060F	3	E		TB5060F	4	E		YC060-YC070, YD160-YR328
ZZQI	02		ZK		0-0	24-51-11	TB5060F	5	E		TB5060F	6	E		YC051-YC059, YD151-YD158
ZZQI	02		ZK		0-0	24-51-14	TB5060F	5	E		TB5060F	6	E		YC060-YC070, YD160-YR328
ZZQJ	02		ZK		0-0	24-61-22	TB5060F	9	E		TB5060F	10	E		ALL
ZZQK	02		ZK		0-0	24-51-21	TB5060E	1	E		TB5060E	2	E		YC051-YC059, YD151-YD158
ZZQK	02		ZK		0-0	24-51-24	TB5060E	1	E		TB5060E	2	E		YC060-YC070, YD160-YR328
ZZQL	02		ZK		0-0	24-51-21	TB5060E	3	E		TB5060E	4	E		YC051-YC059, YD151-YD158
ZZQL	02		ZK		0-0	24-51-24	TB5060E	3	E		TB5060E	4	E		YC060-YC070, YD160-YR328
ZZQM	02		ZK		0-0	24-51-21	TB5060E	5	E		TB5060E	6	E		YC051-YC059, YD151-YD158
ZZQM	02		ZK		0-0	24-51-24	TB5060E	5	E		TB5060E	6	E		YC060-YC070, YD160-YR328
ZZQN	02		ZK		0-0	24-61-52	TB5060E	10	E		TB5060E	11	E		ALL
ZZQP	02		ZK		0-0	24-61-22	TB5060H	5	E		TB5060H	6	E		ALL
ZZQQ	02		ZK		0-0	24-61-24	TB5060D	9	E		TB5060D	10	E		ALL
ZZQR	02		ZK		0-0	24-61-61	TB5060C	9	E		TB5060C	10	E		YC062-YR328
ZZQT	02		ZK		0-0	24-51-11	TB5060K	1	E		TB5060K	2	E		YC051-YC059
ZZQT	02		ZK		0-0	24-51-15	TB5060K	1	E		TB5060K	2	E		YC060-YR328
ZZQU	02		ZK		0-0	24-51-11	TB5060K	3	E		TB5060K	4	E		YC051-YC059, YD154-YD158
ZZQU	02		ZK		0-0	24-51-15	TB5060K	3	E		TB5060K	4	E		YC060-YD153, YD160-YR328
ZZQV	02		ZK		0-0	24-51-11	TB5060K	5	E		TB5060K	6	E		YC051-YC059
ZZQV	02		ZK		0-0	24-51-15	TB5060K	5	E		TB5060K	6	E		YC060-YR328
ZZQW	02		ZK		0-0	24-51-21	TB5060K	7	E		TB5060K	8	E		YC051-YC059, YD151-YD158

WIRE LIST

D280A108

91-21-11

Section W0040

Page 21

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0040	286A0040			P6 (BUS SIDE) (continued)											
ZZQW	02		ZK		0-0	24-51-25	TB5060K	7	E		TB5060K	8	E		YC060-YC070, YD160-YR328
ZZQX	02		ZK		0-0	24-51-21	TB5060K	9	E		TB5060K	10	E		YC051-YC059, YD151-YD158
ZZQX	02		ZK		0-0	24-51-25	TB5060K	9	E		TB5060K	10	E		YC060-YC070, YD160-YR328
ZZQY	02		ZK		0-0	24-51-21	TB5060K	11	E		TB5060K	12	E		YC051-YC059, YD151-YD158
ZZQY	02		ZK		0-0	24-51-25	TB5060K	11	E		TB5060K	12	E		YC060-YC070, YD160-YR328
ZZXA	02		ZA		0-0	24-51-21	C01239	=B	D		C00120	=B	D		YC051-YC059
ZZXA	02		ZA		0-0	24-51-24	C00120	=B	D		C01239	=B	D		YC060-YC070, YD160-YR328
ZZXA	02		ZA		0-0	24-51-21	C00120	=B	D		C01239	=B	D		YD151-YD158
ZZXB	02		ZA		0-0	24-51-11	C01483	=B	D		C01216	=B	D		YD158
ZZXB	02		ZA		0-0	24-51-14	C01483	=B	D		C01216	=B	D		YD160-YR328
ZZXE	02		ZA		0-0	24-61-24	C01515	=B	D		C01630	=B	D		YD157-YR328
ZZXF	02		ZA		0-0	24-61-24	C01064	=B	D		C01631	=B	D		YD157-YR328
ZZXH	02		ZA		0-0	24-51-21	C01008	=B	D		C01262	=B	D		YC051-YC059, YD151-YD158
ZZXH	02		ZA		0-0	24-51-24	C01008	=B	D		C01262	=B	D		YC060-YC070, YD160-YR328
ZZXI	02		ZA		0-0	24-51-14	C01216	=B	D		C01196	=B	D		YN236-YR328
ZZXJ	02		ZA		0-0	24-51-21	C00840	A1	D		C00841	A1	D		YC051-YC059, YD151-YD158
ZZXJ	02		ZA		0-0	24-51-24	C00840	A1	D		C00841	A1	D		YC060-YC070, YD160-YR328
ZZXK	02		ZA		0-0	24-51-21	C01315	=B	D		C00840	A1	D		YC051-YC059, YD151-YD158
ZZXK	02		ZA		0-0	24-51-24	C01315	=B	D		C00840	A1	D		YC060-YC070, YD160-YR328
ZZXL	02		ZA		0-0	24-51-21	C00840	B1	D		C00841	B1	D		YC051-YC059, YD151-YD158
ZZXL	02		ZA		0-0	24-51-24	C00840	B1	D		C00841	B1	D		YC060-YC070, YD160-YR328
ZZXM	02		ZA		0-0	24-51-21	C01391	=B	D		C00840	B1	D		YC051-YC059, YD151-YD158
ZZXM	02		ZA		0-0	24-51-24	C01391	=B	D		C00840	B1	D		YC060-YC070, YD160-YR328

WIRE LIST
D280A108

91-21-11
Section W0040
Page 22
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0040		286A0040			P6 (BUS SIDE) (continued)											
ZZXN		02		ZA		0-0	24-51-21	C00840		C1	D	C00841		C1	D	YC051-YC059
ZZXN		02		ZA		0-0	24-51-24	C00840		C1	D	C00841		C1	D	YC060-YR328
ZZXV		02		ZA		0-0	24-51-24	C00258		=B	D	C00400		=B	D	YN231-YN501
ZZXW		02		ZA		0-0	24-53-11	C00219		=B	D	C00323		=B	D	ALL
ZZXX		02		ZA		0-0	24-53-11	C00335		=B	D	C00284		=B	D	ALL
ZZXY		02		ZA		0-0	24-53-11	C00309		=B	D	C00335		=B	D	ALL
ZZXZ		02		ZA		0-0	24-54-11	C01424		=B	D	C00072		=B	D	ALL
ZZYA		02		ZA		0-0	24-61-32	C00561		=B	D	C00347		=B	D	ALL
ZZYB		02		ZA		0-0	24-61-32	C00240		=B	D	C00561		=B	D	ALL
ZZYC		02		ZA		0-0	24-61-33	C01432		=B	D	C00451		=B	D	ALL
ZZYD		02		ZA		0-0	24-61-33	C00196		=B	D	C00451		=B	D	ALL
ZZYF		02		ZA		0-0	24-61-33	C00131		=B	D	C01277		=B	D	ALL
ZZYG		02		ZA		0-0	24-61-33	C00131		=B	D	C00161		=B	D	ALL
ZZYH		02		ZA		0-0	24-61-33	C00282		=B	D	C00129		=B	D	ALL
ZZYI		02		ZA		0-0	24-61-22	C00195		=B	D	C00569		=B	D	ALL
ZZYJ		02		ZA		0-0	24-61-32	C01286		=B	D	C01269		=B	D	YC065, YL964-YL999, YN236-YR328
ZZYK		02		ZA		0-0	24-61-24	C01364		=B	D	C01360		=B	D	YC051-YL954, YN231-YN235
ZZYL		02		ZA		0-0	24-61-24	C00166		=B	D	C01206		=B	D	ALL
ZZYM		02		ZA		0-0	24-61-24	C00560		=B	D	C00239		=B	D	YC051-YL954, YN231-YN235
ZZYN		02		ZA		0-0	24-61-24	C00204		=B	D	C00207		=B	D	YC051-YL954, YN231-YN235
ZZYO		02		ZA		0-0	24-61-24	C01377		=B	D	C01952		=B	D	YN501-YR328
ZZYP		02		ZA		0-0	24-61-24	C01464		=B	D	C01004		=B	D	ALL
ZZYR		02		ZA		0-0	24-61-51	C00134		=B	D	C01328		=B	D	ALL
ZZYS		02		ZA		0-0	24-61-22	C00211		=B	D	C01081		=B	D	ALL
ZZYU		02		ZA		0-0	24-61-24	C00440		=B	D	C01468		=B	D	ALL
ZZYZ		02		ZA		0-0	24-61-32	C00277		=B	D	C01319		=B	D	ALL
ZZZB		02		ZA		0-0	24-61-52	C01466		=B	D	C01290		=B	D	YC051-YL999, YR301-YR328
ZZZB		02		ZA		0-0	24-61-52	C01290		=B	D	C01466		=B	D	YN231-YN501
ZZZC		02		ZA		0-0	24-61-24	C01116		=B	D	C01436		=B	D	YC051-YL999, YR301-YR328
ZZZC		02		ZA		0-0	24-61-24	C01436		=B	D	C01116		=B	D	YN231-YN501
ZZZD		02		ZA		0-0	24-61-22	C01117		=B	D	C03064		=B	D	ALL
ZZZE		02		ZA		0-0	24-51-21	C01379		=B	D	C01480		=B	D	YC051-YC059

WIRE LIST

D280A108

91-21-11

Section W0040

Page 23

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0040	286A0040				P6 (BUS SIDE) (continued)										
ZZZE	02		ZA		0-0	24-51-24	C01480	=B	D		C01379	=B	D		YC060-YC070, YD160-YR328
ZZZE	02		ZA		0-0	24-51-21	C01480	=B	D		C01379	=B	D		YD151-YD158
ZZZP	02		ZA		0-0	24-61-24	C01584	=B	D		C01377	=B	D		YC060-YN260
ZZZQ	02		ZB		0-0	24-61-24	C01468	=B	D		C01611	=B	D		YC051-YC065
W0041	286A0041				P61 - DATA LOADER CONTROL PANEL										
0001	22		PA		1-6	34-61-18	D02875	20			D01907	20			YC051-YC058
0001	22		PA		1-9	31-32-15	D01907	20			D02875	20			YC059-YD170
0001	22		PA		6-4	31-32-15	D10903	20			D01907	20			YL951-YN260
0001	22		PA		6-2	31-32-15	D10903	20			D01907	20			YN501-YR328
0002	22		PA		8-11	34-61-18	D01907	22			GD00624	AC..	1		YC051-YC057
0002	22		PA		9-0	34-61-18	D01907	22			GD00624	AC..	1		YC058
0002	22		PA		1-9	31-32-15	D01907	22			D02875	22			YC059-YD170
0002	22		PA		9-1	31-32-15	D01907	22			GD00624	AC..	1		YL951-YN260
0002	22		PA		8-11	31-32-15	D01907	22			GD00624	AC..	1		YN501-YR328
0005	22		PA		1-6	34-61-18	D01907	50			D02875	50			YC051-YC058
0005	22		PA		1-9	31-32-15	D01907	50			D02875	50			YC059-YD170
0005	22		PA		6-4	31-32-15	D10903	50			D01907	50			YL951-YN260
0005	22		PA		6-2	31-32-15	D10903	50			D01907	50			YN501-YR328
0006	22		PA		1-6	34-61-18	D01907	51			D02875	51			YC051-YC058
0006	22		PA		1-9	31-32-15	D01907	51			D02875	51			YC059-YD170
0006	22		PA		6-4	31-32-15	D10903	51			D01907	51			YL951-YN260
0006	22		PA		6-2	31-32-15	D10903	51			D01907	51			YN501-YR328
0007	22		PA		1-6	34-61-18	D01907	52			D02875	52			YC051-YC058
0007	22		PA		1-9	31-32-15	D01907	52			D02875	52			YC059-YD170
0007	22		PA		6-4	31-32-15	D10903	52			D01907	52			YL951-YN260
0007	22		PA		6-2	31-32-15	D10903	52			D01907	52			YN501-YR328
0008	22		PA		1-6	34-61-18	D01907	53			D02875	53			YC051-YC058
0008	22		PA		1-9	31-32-15	D01907	53			D02875	53			YC059-YD170
0008	22		PA		6-4	31-32-15	D10903	53			D01907	53			YL951-YN260
0008	22		PA		6-2	31-32-15	D10903	53			D01907	53			YN501-YR328
0009	22		PA		2-1	34-61-18	D01907	21			GD00061	ST..	E		YC051-YC058
0009	22		PA		1-9	31-32-15	D01907	21			D02875	21			YC059-YD170
0009	22		PA		2-2	31-32-15	D01907	21			GD00061	ST..	E	*1	YL951-YN260
0009	22		PA		2-0	31-32-15	D01907	21			GD00061	ST..	E	*1	YN501-YR328
0010	20		PA		4-5	34-61-18	D02877	11			TB5060B	9	E		YC051-YC058
0010	20		PA		4-6	31-32-15	D02879	28			TB5060B	9	E		YC059-YN260
0010	20		PA		4-4	31-32-15	D02879	28			TB5060B	9	E		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0040

Page 24

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W0041	286A0041				P61 - DATA LOADER CONTROL PANEL (continued)										
0011	22		PA	2-5	34-61-18	D02879		2			GD00061	ST..	E	*1	YC051-YC058
0011	22		PA	9-6	31-32-15	D02879		13			GD00624	AC..	1		YC059-YN260
0011	22		PA	9-3	31-32-15	D02879		13			GD00624	AC..	1		YN501-YR301
0011	22		PA	9-4	31-32-15	D02879		13			GD00624	AC..	1		YR303-YR328
0012	20		PA	9-4	34-61-18	D02877		12			GD00624	DC..	1		YC051-YC057
0012	20		PA	9-5	34-61-18	D02877		12			GD00624	DC..	1		YC058
0012	22		PA	2-6	31-32-15	D02875		18			GD00061	ST..	E		YC059-YD170
0012	22		PA	2-6	31-32-15	D02875		18			GD00061	ST..	E	*1	YL951-YN260
0012	22		PA	2-5	31-32-15	D02875		18			GD00061	ST..	E	*1	YN501-YR328
0013	22		PA	10-4	34-61-18	D02877		7			D40625J				YC051-YC057
0013	22		PA	10-5	34-61-18	D02877		7			D40625J				YC058
0013	22		PA	1-9	31-32-15	D01907		19			D02875				YC059-YD170
0014	22		PA	10-1	34-61-18	D10193		21			D40625J				YC051-YC057
0014	22		PA	10-3	34-61-18	D10193		21			D40625J				YC058
0015	20		PA	9-2	34-61-18	D10193		22			GD00624	DC..	1		YC051-YC057
0015	20		PA	9-3	34-61-18	D10193		22			GD00624	DC..	1		YC058
0016	24		PK	10-4	31-35-01	D02877		16			D40625J				YC051-YC057
0016	24		PK	10-5	31-35-01	D02877		16			D40625J				YC058
0016	24		PK	10-5	31-35-01	D02879		19			D40625J				YC059-YD157
0016	24		PK	10-2	31-35-01	D02879		19			D40625J				YD158-YD170
0016	24		PK	9-7	31-35-01	D02879		19			D40625J				YL951-YN260
0016	24		PK	9-9	31-35-01	D02879		19			D40625J				YN501-YR328
0017	24		PK	10-4	31-35-01	D02877		17			D40625J				YC051-YC057
0017	24		PK	10-5	31-35-01	D02877		17			D40625J				YC058
0017	24		PK	10-5	31-35-01	D02879		20			D40625J				YC059-YD157
0017	24		PK	10-2	31-35-01	D02879		20			D40625J				YD158-YD170
0017	24		PK	9-7	31-35-01	D02879		20			D40625J				YL951-YN260
0017	24		PK	9-9	31-35-01	D02879		20			D40625J				YN501-YR328
0018	24		PK	10-4	31-35-01	D02877		19			D40625J				YC051-YC057
0018	24		PK	10-5	31-35-01	D02877		19			D40625J				YC058
0018	24		PK	10-5	31-35-01	D02879		7			D40625J				YC059-YD157
0018	24		PK	10-2	31-35-01	D02879		7			D40625J				YD158-YD170
0018	24		PK	9-7	31-35-01	D02879		7			D40625J				YL951-YN260
0018	24		PK	9-9	31-35-01	D02879		7			D40625J				YN501-YR328
0019	22		PA	10-4	34-58-11	D02271		3			D40623J				YC051-YC057
0019	22		PA	10-5	34-58-11	D02271		3			D40623J				YC058
0019	22		PA	8-3	34-58-11	D02271		3			D40623J				YC059-YN260
0019	22		PA	8-2	34-58-11	D02271		3			D40623J				YN501-YR328
0020	22		G5	10-4	34-21-21	D02271		18			D40623J				YC051-YC057

WIRE LIST

D280A108

91-21-11

Section W0040

Page 25

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0041	286A0041			P61 - DATA LOADER CONTROL PANEL (continued)											
0020	22		G5		10-5	34-21-21	D02271		18		D40623J	2			YC058
0020	22		G5		8-3	34-21-21	D02271		18		D40623J	2			YC059-YN260
0020	22		G5		8-2	34-21-21	D02271		18		D40623J	2			YN501-YR328
0021	22		G5		10-4	34-21-21	D02271		17		D40623J	3			YC051-YC057
0021	22		G5		10-5	34-21-21	D02271		17		D40623J	3			YC058
0021	22		G5		8-3	34-21-21	D02271		17		D40623J	3			YC059-YN260
0021	22		G5		8-2	34-21-21	D02271		17		D40623J	3			YN501-YR328
0022	22		G5		10-4	34-21-21	D02271		15		D40623J	4			YC051-YC057
0022	22		G5		10-5	34-21-21	D02271		15		D40623J	4			YC058
0022	22		G5		8-3	34-21-21	D02271		15		D40623J	4			YC059-YN260
0022	22		G5		8-2	34-21-21	D02271		15		D40623J	4			YN501-YR328
0023	22		G5		10-4	34-21-21	D02271		16		D40623J	5			YC051-YC057
0023	22		G5		10-5	34-21-21	D02271		16		D40623J	5			YC058
0023	22		G5		8-3	34-21-21	D02271		16		D40623J	5			YC059-YN260
0023	22		G5		8-2	34-21-21	D02271		16		D40623J	5			YN501-YR328
0024	22		PA		10-8	34-21-11	D02269		17		D40625J	1			YC051-YC057
0024	22		PA		10-9	34-21-11	D02269		17		D40625J	1			YC058
0024	22		PA		8-8	34-21-11	D02269		17		D40625J	1			YC059-YD157
0024	22		PA		8-5	34-21-11	D02269		17		D40625J	1			YD158-YD170
0024	22		PA		7-9	34-21-11	D02269		17		D40625J	1			YL951-YN260
0024	22		PA		8-0	34-21-11	D02269		17		D40625J	1			YN501-YR328
0025	22		PA		10-8	34-21-11	D02269		15		D40625J	2			YC051-YC057
0025	22		PA		10-9	34-21-11	D02269		15		D40625J	2			YC058
0025	22		PA		8-8	34-21-11	D02269		15		D40625J	2			YC059-YD157
0025	22		PA		8-5	34-21-11	D02269		15		D40625J	2			YD158-YD170
0025	22		PA		7-9	34-21-11	D02269		15		D40625J	2			YL951-YN260
0025	22		PA		8-0	34-21-11	D02269		15		D40625J	2			YN501-YR328
0026	22		PA		10-8	34-21-11	D02269		16		D40625J	3			YC051-YC057
0026	22		PA		10-9	34-21-11	D02269		16		D40625J	3			YC058
0026	22		PA		8-8	34-21-11	D02269		16		D40625J	3			YC059-YD157
0026	22		PA		8-5	34-21-11	D02269		16		D40625J	3			YD158-YD170
0026	22		PA		7-9	34-21-11	D02269		16		D40625J	3			YL951-YN260
0026	22		PA		8-0	34-21-11	D02269		16		D40625J	3			YN501-YR328
0027	22		PA		10-8	34-21-11	D02269		18		D40625J	4			YC051-YC057
0027	22		PA		10-9	34-21-11	D02269		18		D40625J	4			YC058
0027	22		PA		8-8	34-21-11	D02269		18		D40625J	4			YC059-YD157
0027	22		PA		8-5	34-21-11	D02269		18		D40625J	4			YD158-YD170
0027	22		PA		7-9	34-21-11	D02269		18		D40625J	4			YL951-YN260
0027	22		PA		8-0	34-21-11	D02269		18		D40625J	4			YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0040

Page 26

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To					
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W0041	286A0041			P61 - DATA LOADER CONTROL PANEL (continued)												
0028	22		PA		2-10	34-21-16	D02269		23			SM00003		S		YC051-YC057
0028	22		PA		3-6	34-21-16	D02269		23			SM00003		S		YC058
0028	22		PA		3-11	34-21-16	D02269		23			SM00003		S		YC059-YN260
0028	22		PA		2-0	34-21-16	D02269		23			SM00003		S		YN501-YR328
0029	22		PA		2-10	34-21-16	D02271		23			SM00003		S		YC051-YC057
0029	22		PA		3-6	34-21-16	D02271		23			SM00003		S		YC058
0029	22		PA		3-11	34-21-16	D02271		23			SM00003		S		YC059-YN260
0029	22		PA		2-0	34-21-16	D02271		23			SM00003		S		YN501-YR328
0030	24		PK		10-3	31-62-15	D02879		17			D40625J	15			YC051-YC057
0030	24		PK		10-4	31-62-15	D02879		17			D40625J	15			YC058
0030	24		PK		10-6	31-62-15	D02877		18			D40625J	15			YC059-YD157
0030	24		PK		10-3	31-62-15	D02877		18			D40625J	15			YD158-YD170
0030	24		PK		9-8	31-62-15	D02877		18			D40625J	15			YL951-YN260
0030	24		PK		9-9	31-62-15	D02877		18			D40625J	15			YN501-YR328
0031	22		PA		8-4	34-21-16	D40625J		5			SM00003		S		YC051-YC057
0031	22		PA		7-10	34-21-16	D40625J		5			SM00003		S		YC058-YD157
0031	22		PA		7-7	34-21-16	D40625J		5			SM00003		S		YD158-YD170
0031	22		PA		6-11	34-21-16	D40625J		5			SM00003		S		YL951-YN260
0031	22		PA		6-6	34-21-16	D40625J		5			SM00003		S		YN501-YR328
0032	20		CQ		3-9	33-18-41	D02269		20			TB5060B	7	E		YC051-YC058
0032	20		CQ		7-7	33-18-41	D02269		20			TB5060B	7	E		YC059-YN260
0032	20		CQ		7-6	33-18-41	D02269		20			TB5060B	7	E		YN501-YR328
0033	20		CQ		3-10	31-52-71	D02269		21			TB5060B	4	E		YC051-YC058
0033	20		CQ		7-8	31-52-71	D02269		21			TB5060B	4	E		YC059-YN260
0033	20		CQ		7-7	31-52-71	D02269		21			TB5060B	4	E		YN501-YR328
0034	20		CQ		3-9	31-52-71	D02269		3			TB5060B	5	E		YC051-YC058
0034	20		CQ		7-8	31-52-71	D02269		3			TB5060B	5	E		YC059-YN260
0034	20		CQ		7-7	31-52-71	D02269		3			TB5060B	5	E		YN501-YR328
0035	20		CQ		3-9	31-52-71	D02269		9			TB5060B	6	E		YC051-YC058
0035	20		CQ		7-7	31-52-71	D02269		9			TB5060B	6	E		YC059-YN260
0035	20		CQ		7-6	31-52-71	D02269		9			TB5060B	6	E		YN501-YR328
0036	24		G6		9-9	31-62-25	D10193		17			D40623J	8			YC051-YC057
0036	24		G6		9-10	31-62-25	D10193		17			D40623J	8			YC058
0036	24		G6		10-0	31-62-25	D10193		18			D40623J	8			YC059-YN260
0036	24		G6		9-9	31-62-25	D10193		18			D40623J	8			YN501-YR328
0037	20		PA		3-7	34-21-11	D02269		8			GD00061	ST..	E		YC051-YC058
0037	20		PA		6-5	34-21-11	D02269		8			GD00061	ST..	E		YC059-YN260
0037	20		PA		6-3	34-21-11	D02269		8			GD00061	ST..	E		YN501-YR328
0038	20		CQ		9-8	31-52-71	D02269		4			GD00624	DC..	1		YC051-YC057

WIRE LIST

D280A108

91-21-11

Section W0040

Page 27

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity			
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice	
W0041	286A0041				P61 - DATA LOADER CONTROL PANEL (continued)											
0038	20		CQ		9-9	31-52-71	D02269			4		GD00624	DC..	1		YC058
0038	20		CQ		7-8	31-52-71	D02269			4		GD00624	DC..	1		YC059-YN260
0038	20		CQ		7-7	31-52-71	D02269			4		GD00624	DC..	1		YN501-YR328
0039	24		PK		10-3	23-27-11	D02879			8		D40625J	31			YC051-YC057
0039	24		PK		10-4	23-27-11	D02879			8		D40625J	31			YC058
0039	24		PK		10-6	23-27-11	D02877			19		D40625J	31			YC059-YD157
0039	24		PK		10-3	23-27-39	D02877			19		D40625J	31			YD158-YD170
0039	24		PK		9-8	23-27-39	D02877			19		D40625J	31			YL951-YN260
0039	24		PK		9-9	23-27-39	D02877			19		D40625J	31			YN501-YR328
0041	20		PA		2-1	34-61-18	D01907				AE	GD00061	ST..	E	*1	YC051-YC058
0041	20		PA		2-2	31-32-15	D01907				AE	GD00061	ST..	E	*2	YC059-YN260
0041	20		PA		2-0	31-32-15	D01907				AE	GD00061	ST..	E	*2	YN501-YR328
0042	20		PA		2-1	34-61-18	D01907				AB	GD00061	ST..	E	*2	YC051-YC058
0042	20		PA		2-2	31-32-15	D01907				AB	GD00061	ST..	E	*2	YC059-YN260
0042	20		PA		2-0	31-32-15	D01907				AB	GD00061	ST..	E	*2	YN501-YR328
0043	20		PA		2-1	34-61-18	D01907				AC	GD00061	ST..	E	*2	YC051-YC058
0043	20		PA		2-2	31-32-15	D01907				AC	GD00061	ST..	E	*2	YC059-YN260
0043	20		PA		2-0	31-32-15	D01907				AC	GD00061	ST..	E	*2	YN501-YR328
0046	22		PA		10-3	34-61-18	D40625J			8		D02879	21			YC051-YC057
0046	22		PA		10-4	34-61-18	D40625J			8		D02879	21			YC058
0046	22		PA		10-5	31-32-15	D40625J			8		D02879	27			YC059-YD157
0046	22		PA		10-2	31-32-15	D40625J			8		D02879	27			YD158-YD170
0046	22		PA		9-7	31-32-15	D40625J			8		D02879	27			YL951-YN260
0046	22		PA		9-9	31-32-15	D40625J			8		D02879	27			YN501-YR328
0048	22		PA		10-1	23-15-15	D10193			3		D40625J	40			YC051-YC057
0048	22		PA		10-3	23-15-15	D10193			3		D40625J	40			YC058
0048	22		PA		10-6	23-15-15	D02877			16		D40625J	40			YC059-YD157
0049	22		PA		6-7	31-32-15	D10901			20		D02875	20			YL951-YN260
0049	22		PA		6-6	31-32-15	D10901			20		D02875	20			YN501-YR328
0050	22		PA		6-7	31-32-15	D10901			50		D02875	50			YL951-YN260
0050	22		PA		6-6	31-32-15	D10901			50		D02875	50			YN501-YR328
0051	22		PA		6-7	31-32-15	D10901			51		D02875	51			YL951-YN260
0051	22		PA		6-6	31-32-15	D10901			51		D02875	51			YN501-YR328
0052	22		PA		6-7	31-32-15	D10901			52		D02875	52			YL951-YN260
0052	22		PA		6-6	31-32-15	D10901			52		D02875	52			YN501-YR328
0053	22		PA		6-7	31-32-15	D10901			53		D02875	53			YL951-YN260
0053	22		PA		6-6	31-32-15	D10901			53		D02875	53			YN501-YR328
0054	22		PA		4-2	31-32-15	D10903			30		TB0610X	A009	1A		YL951-YN260
0054	22		PA		4-1	31-32-15	D10903			30		TB0610X	A009	1A		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0040

Page 28

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W0041	286A0041				P61 - DATA LOADER CONTROL PANEL (continued)											
0055	20		CQ		9-8	34-58-21	D02271		21		GD00624	DC..	1		YC051-YC052	
0055	20		G5		9-8	34-58-21	D02271		21		GD00624	DC..	1		YC053-YC057	
0055	20		G5		9-9	34-58-21	D02271		21		GD00624	DC..	1		YC058	
0055	20		G5		7-8	34-58-21	D02271		21		GD00624	DC..	1		YC059-YN260	
0055	20		G5		7-7	34-58-21	D02271		21		GD00624	DC..	1		YN501-YR328	
0056	22		PA		6-7	31-32-15	D10901		19		D02875		19		YL951-YN260	
0056	22		PA		6-6	31-32-15	D10901		19		D02875		19		YN501-YR328	
0057	22		PA		6-7	31-32-15	D10901		21		D02875		21		YL951-YN260	
0057	22		PA		6-6	31-32-15	D10901		21		D02875		21		YN501-YR328	
0058	22		PA		6-7	31-32-15	D10901		22		D02875		22		YL951-YN260	
0058	22		PA		6-6	31-32-15	D10901		22		D02875		22		YN501-YR328	
0089	24		PK		10-6	34-61-18	D02877		42		D40625J		44		YC059-YD157	
0089	24		PK		10-3	34-61-18	D02877		42		D40625J		44		YD158-YD170	
0089	24		PK		9-8	34-61-18	D02877		42		D40625J		44		YL951-YN260	
0089	24		PK		9-9	34-61-18	D02877		42		D40625J		44		YN501-YR328	
0090	24		PK		10-0	34-61-18	D10193		9		D40623J		18		YC059-YN260	
0090	24		PK		9-9	34-61-18	D10193		9		D40623J		18		YN501-YR328	
0091	24		PK		10-6	34-61-26	D02877		2		D40625J		41		YC059-YD157	
0091	24		PK		10-3	34-61-26	D02877		2		D40625J		41		YD158-YD170	
0091	24		PK		9-8	34-61-26	D02877		2		D40625J		41		YL951-YN260	
0091	24		PK		9-9	34-61-26	D02877		2		D40625J		41		YN501-YR328	
0092	24		PK		10-0	34-61-26	D10193		7		D40623J		23		YC059-YN260	
0092	24		PK		9-9	34-61-26	D10193		7		D40623J		23		YN501-YR328	
0093	24		PK		10-6	22-11-53	D02877		54		D40625J		49		YC059-YD157	
0093	24		PK		10-3	22-11-53	D02877		54		D40625J		49		YD158-YD170	
0093	24		PK		9-8	22-11-53	D02877		54		D40625J		49		YL951-YN260	
0093	24		PK		9-9	22-11-53	D02877		54		D40625J		49		YN501-YR328	
0094	24		PK		10-6	22-11-53	D02877		15		D40625J		50		YC059-YD157	
0094	24		PK		10-3	22-11-53	D02877		15		D40625J		50		YD158-YD170	
0094	24		PK		9-8	22-11-53	D02877		15		D40625J		50		YL951-YN260	
0094	24		PK		9-9	22-11-53	D02877		15		D40625J		50		YN501-YR328	
0095	24		PK		10-6	22-11-53	D02877		31		D40625J		51		YC059-YD157	
0095	24		PK		10-3	22-11-53	D02877		31		D40625J		51		YD158-YD170	
0095	24		PK		9-8	22-11-53	D02877		31		D40625J		51		YL951-YN260	
0095	24		PK		9-9	22-11-53	D02877		31		D40625J		51		YN501-YR328	
0096	24		PK		10-5	22-11-53	D02879		11		D40625J		52		YC059-YD157	
0096	24		PK		10-2	22-11-53	D02879		11		D40625J		52		YD158-YD170	
0096	24		PK		9-7	22-11-53	D02879		11		D40625J		52		YL951-YN260	
0096	24		PK		9-9	22-11-53	D02879		11		D40625J		52		YN501-YR328	

WIRE LIST

D280A108

91-21-11

Section W0040

Page 29

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0041	286A0041				P61 - DATA LOADER CONTROL PANEL (continued)											
0097	24		PK		10-0	22-11-53		D10193		5		D40623J	28			YC059-YN260
0097	24		PK		9-9	22-11-53		D10193		5		D40623J	28			YN501-YR328
0098	24		PK		10-0	22-11-53		D10193		1		D40623J	29			YC059-YN260
0098	24		PK		9-9	22-11-53		D10193		1		D40623J	29			YN501-YR328
0099	24		PK		10-0	22-11-53		D10193		32		D40623J	30			YC059-YN260
0099	24		PK		9-9	22-11-53		D10193		32		D40623J	30			YN501-YR328
0103	22		PA		8-3	34-58-11		D02271		8		D40623J	21			YL951-YN260
0103	22		PA		8-2	34-58-11		D02271		8		D40623J	21			YN501-YR328
0104	20		G5		7-8	34-58-11		D02271		9		GD00624	DC..	1		YL951-YN260
0104	20		G5		7-7	34-58-11		D02271		9		GD00624	DC..	1		YN501-YR328
0105	22		PA		8-3	34-58-11		D02269		12		D40623J	22			YL951-YN260
0105	22		PA		8-2	34-58-11		D02269		12		D40623J	22			YN501-YR328
0106	20		G5		7-8	34-58-11		D02269		11		GD00624	DC..	1		YL951-YN260
0106	20		G5		7-7	34-58-11		D02269		11		GD00624	DC..	1		YN501-YR328
2001B	22		PB	EA	7-2	23-51-31		D04151J		2		SM00001		S		YC051-YC057
2001B	22		PB	EA	6-5	23-51-31		D04151J		2		SM00001		S		YC058-YN260
2001B	22		PB	EA	7-0	23-51-31		D04151J		2		SM00001		S		YN501-YR328
2001R	22		PB	EA	0-0	23-51-31		D04151J		1		SM00002		S		ALL
2003B	24		PL	EC	4-6	23-51-31		D04151J		4		D04005P	= 1	VR		YC051-YN260
2003B	24		PL	EC	4-8	23-51-31		D04151J		4		D04005P	= 1	VR		YN501-YR328
2003R	24		PL	EC	0-0	23-51-31		D04151J		3		D04003J	= 1	VY		ALL
2501B	22		X2	AA	1-6	34-61-18		D02875		9		D01907	9			YC051-YC058
2501B	22		X2	AA	1-9	31-32-15		D02875		9		D01907	9			YC059-YD170
2501B	22		X2	AA	6-4	31-32-15		D10903		9		D01907	9			YL951-YN260
2501B	22		X2	AA	6-2	31-32-15		D10903		9		D01907	9			YN501-YR328
2501R	22		X2	AA	0-0	34-61-18		D02875		8		D01907	8			YC051-YC058
2501R	22		X2	AA	0-0	31-32-15		D02875		8		D01907	8			YC059-YD170
2501R	22		X2	AA	0-0	31-32-15		D10903		8		D01907	8			YL951-YR328
2501Z				AA	0-0	34-61-18		D02875		DED		D01907			AE	YC051-YC058
2501Z				AA	0-0	31-32-15		D02875		DED		D01907			AE	YC059-YD170
2501Z				AA	0-0	31-32-15		D10903		DED		D01907			AE	YL951-YR328
2502B	22		X2	AB	1-6	34-61-18		D02875		11		D01907	11			YC051-YC058
2502B	22		X2	AB	1-9	31-32-15		D02875		11		D01907	11			YC059-YD170
2502B	22		X2	AB	6-4	31-32-15		D10903		11		D01907	11			YL951-YN260
2502B	22		X2	AB	6-2	31-32-15		D10903		11		D01907	11			YN501-YR328
2502R	22		X2	AB	0-0	34-61-18		D02875		10		D01907	10			YC051-YC058
2502R	22		X2	AB	0-0	31-32-15		D02875		10		D01907	10			YC059-YD170
2502R	22		X2	AB	0-0	31-32-15		D10903		10		D01907	10			YL951-YR328
2502Z				AB	0-0	34-61-18		D02875		DED		D01907			AB	YC051-YC058

WIRE LIST

D280A108

91-21-11

Section W0040

Page 30

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		Diagram	From			To					
	Wire No.	GA	CO TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W0041	286A0041				P61 - DATA LOADER CONTROL PANEL (continued)											
2502Z				AB	0-0	31-32-15	D02875		DED			D01907			AB	YC059-YD170
2502Z				AB	0-0	31-32-15	D10903		DED			D01907			AB	YL951-YR328
2503B	22	X2	AC		1-6	34-61-18	D02875		2			D01907	2			YC051-YC058
2503B	22	X2	AC		1-9	31-32-15	D02875		2			D01907	2			YC059-YD170
2503B	22	X2	AC		6-4	31-32-15	D10903		2			D01907	2			YL951-YN260
2503B	22	X2	AC		6-2	31-32-15	D10903		2			D01907	2			YN501-YR328
2503R	22	X2	AC		0-0	34-61-18	D02875		1			D01907	1			YC051-YC058
2503R	22	X2	AC		0-0	31-32-15	D02875		1			D01907	1			YC059-YD170
2503R	22	X2	AC		0-0	31-32-15	D10903		1			D01907	1			YL951-YR328
2503Z				AC	0-0	34-61-18	D02875		DED			D01907			AC	YC051-YC058
2503Z				AC	0-0	31-32-15	D02875		DED			D01907			AC	YC059-YD170
2503Z				AC	0-0	31-32-15	D10903		DED			D01907			AC	YL951-YR328
2504B	22	X2	AD		10-4	34-61-18	D02877		5			D40625J	10			YC051-YC057
2504B	22	X2	AD		10-5	34-61-18	D02877		5			D40625J	10			YC058
2504B	22	X2	AD		10-5	31-32-15	D02879		29			D40625J	10			YC059-YD157
2504B	22	X2	AD		10-2	31-32-15	D02879		29			D40625J	10			YD158-YD170
2504B	22	X2	AD		9-7	31-32-15	D02879		29			D40625J	10			YL951-YN260
2504B	22	X2	AD		7-10	31-32-15	D02879		29			SP00845		S		YN501-YR301
2504B	22	X2	AD		7-7	31-32-15	D02879		29			TB0610Y	B021	1A		YR303-YR328
2504R	22	X2	AD		0-0	34-61-18	D02877		4			D40625J	9			YC051-YC058
2504R	22	X2	AD		0-0	31-32-15	D02879		14			D40625J	9			YC059-YN260
2504R	22	X2	AD		0-0	31-32-15	D02879		14			SP00843		S		YN501-YR301
2504R	22	X2	AD		0-0	31-32-15	D02879		14			TB0610Y	A021	1A		YR303-YR328
2504Z				AD	0-0	34-61-18	D02877		DED			D40625J	S/R			YC051-YC058
2504Z				AD	0-0	31-32-15	D02879		DED			D40625J	S/R			YC059-YN260
2504Z				AD	0-0	31-32-15	D02879		DED			SP00847		S		YN501-YR301
2504Z				AD	0-0	31-32-15	D02879		DED			GB00610	ST..	1A		YR303-YR328
2505B	22	X2	AE		10-1	34-61-18	D10193		20			D40625J	12			YC051-YC057
2505B	22	X2	AE		10-3	34-61-18	D10193		20			D40625J	12			YC058
2505B	22	X2	AE		10-0	31-32-15	D10193		4			D40623J	17			YC059-YN260
2505B	22	X2	AE		9-9	31-32-15	D10193		4			D40623J	17			YN501-YR328
2505R	22	X2	AE		0-0	34-61-18	D10193		19			D40625J	11			YC051-YC058
2505R	22	X2	AE		0-0	31-32-15	D10193		6			D40623J	16			YC059-YR328
2505Z				AE	0-0	34-61-18	D10193		DED			D40625J	S/R			YC051-YC058
2505Z				AE	0-0	31-32-15	D10193		DED			D40623J	S/R			YC059-YR328
2506B	24	Y2	AF		10-4	31-35-01	D02877		14			D40625J	19			YC051-YC057
2506B	24	Y2	AF		10-5	31-35-01	D02877		14			D40625J	19			YC058
2506B	24	Y2	AF		10-5	31-35-01	D02879		37			D40625J	19			YC059-YD157
2506B	24	Y2	AF		10-2	31-35-01	D02879		37			D40625J	19			YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0040

Page 31

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0041	286A0041			P61 - DATA LOADER CONTROL PANEL (continued)											
2506B	24	Y2	AF		9-7	31-35-01	D02879	37			D40625J	19			YL951-YN260
2506B	24	Y2	AF		9-9	31-35-01	D02879	37			D40625J	19			YN501-YR328
2506R	24	Y2	AF		0-0	31-35-01	D02877	3			D40625J	18			YC051-YC058
2506R	24	Y2	AF		0-0	31-35-01	D02879	55			D40625J	18			YC059-YR328
2506Z			AF		0-0	31-35-01	D02877	DED			D40625J	S/R			YC051-YC058
2506Z			AF		0-0	31-35-01	D02879	DED			D40625J	S/R			YC059-YR328
2507B	24	Y2	AG		10-4	31-35-01	D02877	15			D40625J	21			YC051-YC057
2507B	24	Y2	AG		10-5	31-35-01	D02877	15			D40625J	21			YC058
2507B	24	Y2	AG		10-5	31-35-01	D02879	38			D40625J	21			YC059-YD157
2507B	24	Y2	AG		10-2	31-35-01	D02879	38			D40625J	21			YD158-YD170
2507B	24	Y2	AG		9-7	31-35-01	D02879	38			D40625J	21			YL951-YN260
2507B	24	Y2	AG		9-9	31-35-01	D02879	38			D40625J	21			YN501-YR328
2507R	24	Y2	AG		0-0	31-35-01	D02877	13			D40625J	20			YC051-YC058
2507R	24	Y2	AG		0-0	31-35-01	D02879	39			D40625J	20			YC059-YR328
2507Z			AG		0-0	31-35-01	D02877	DED			D40625J	S/R			YC051-YC058
2507Z			AG		0-0	31-35-01	D02879	DED			D40625J	S/R			YC059-YR328
2508B	24	Y2	AH		10-3	31-62-15	D02879	16			D40625J	17			YC051-YC057
2508B	24	Y2	AH		10-4	31-62-15	D02879	16			D40625J	17			YC058
2508B	24	Y2	AH		10-6	31-62-15	D02877	35			D40625J	17			YC059-YD157
2508B	24	Y2	AH		10-3	31-62-15	D02877	35			D40625J	17			YD158-YD170
2508B	24	Y2	AH		9-8	31-62-15	D02877	35			D40625J	17			YL951-YN260
2508B	24	Y2	AH		9-9	31-62-15	D02877	35			D40625J	17			YN501-YR328
2508R	24	Y2	AH		0-0	31-62-15	D02879	15			D40625J	16			YC051-YC058
2508R	24	Y2	AH		0-0	31-62-15	D02877	58			D40625J	16			YC059-YR328
2508Z			AH		0-0	31-62-15	D02879	DED			D40625J	S/R			YC051-YC058
2508Z			AH		0-0	31-62-15	D02877	DED			D40625J	S/R			YC059-YR328
2509B	24	Y2	AI		9-9	31-62-25	D10193	16			D40623J	7			YC051-YC057
2509B	24	Y2	AI		9-10	31-62-25	D10193	16			D40623J	7			YC058
2509B	24	Y2	AI		10-0	31-62-25	D10193	58			D40623J	7			YC059-YN260
2509B	24	Y2	AI		9-9	31-62-25	D10193	58			D40623J	7			YN501-YR328
2509R	24	Y2	AI		0-0	31-62-25	D10193	15			D40623J	6			YC051-YC058
2509R	24	Y2	AI		0-0	31-62-25	D10193	35			D40623J	6			YC059-YR328
2509Z			AI		0-0	31-62-25	D10193	DED			D40623J	S/R			ALL
2510B	22	X2	AJ		10-4	34-61-18	D02877	9			D40625J	30			YC051-YC057
2510B	22	X2	AJ		10-5	34-61-18	D02877	9			D40625J	30			YC058
2510B	22	X2	AJ		10-6	31-32-15	D02877	5			D40625J	30			YC059-YD157
2510B	22	X2	AJ		10-3	31-32-15	D02877	5			D40625J	30			YD158-YD170
2510B	22	X2	AJ		9-8	31-32-15	D02877	5			D40625J	30			YL951-YN260
2510B	22	X2	AJ		9-9	31-32-15	D02877	5			D40625J	30			YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0040

Page 32

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0041	286A0041			P61 - DATA LOADER CONTROL PANEL (continued)											
2510R	22	X2	AJ		0-0	34-61-18	D02877		10		D40625J		29		YC051-YC058
2510R	22	X2	AJ		0-0	31-32-15	D02877		3		D40625J		29		YC059-YR328
2510Z			AJ		0-0	34-61-18	D02877	DED			D40625J	S/R			YC051-YC058
2510Z			AJ		0-0	31-32-15	D02877	DED			D40625J	S/R			YC059-YR328
2511B	24	Y2	AK		10-8	34-58-11	D02269		2		D40625J		23		YC051-YC057
2511B	24	Y2	AK		10-9	34-58-11	D02269		2		D40625J		23		YC058
2511B	24	Y2	AK		8-8	34-58-11	D02269		2		D40625J		23		YC059-YD157
2511B	24	Y2	AK		8-5	34-58-11	D02269		2		D40625J		23		YD158-YD170
2511B	24	Y2	AK		7-9	34-58-11	D02269		2		D40625J		23		YL951-YN260
2511B	24	Y2	AK		8-0	34-58-11	D02269		2		D40625J		23		YN501-YR328
2511R	24	Y2	AK		0-0	34-58-11	D02269		1		D40625J		22		ALL
2511Z			AK		0-0	34-58-11	D02269	DED			D40625J	S/R			ALL
2512B	24	Y2	AL		10-8	34-58-11	D02269		10		D40625J		35		YC051-YC057
2512B	24	Y2	AL		10-9	34-58-11	D02269		10		D40625J		35		YC058
2512B	24	Y2	AL		8-8	34-58-11	D02269		10		D40625J		35		YC059-YD157
2512B	24	Y2	AL		8-5	34-58-11	D02269		10		D40625J		35		YD158-YD170
2512B	24	Y2	AL		7-9	34-58-11	D02269		10		D40625J		35		YL951-YN260
2512B	24	Y2	AL		8-0	34-58-11	D02269		10		D40625J		35		YN501-YR328
2512R	24	Y2	AL		0-0	34-58-11	D02269		7		D40625J		34		ALL
2512Z			AL		0-0	34-58-11	D02269	DED			D40625J	S/R			ALL
2513B	24	Y2	AM		10-4	34-58-21	D02271		2		D40623J		10		YC051-YC057
2513B	24	Y2	AM		10-5	34-58-21	D02271		2		D40623J		10		YC058
2513B	24	Y2	AM		8-3	34-58-21	D02271		2		D40623J		10		YC059-YN260
2513B	24	Y2	AM		8-2	34-58-21	D02271		2		D40623J		10		YN501-YR328
2513R	24	Y2	AM		0-0	34-58-21	D02271		1		D40623J		9		ALL
2513Z			AM		0-0	34-58-21	D02271	DED			D40623J	S/R			ALL
2514B	24	Y2	AN		10-4	34-58-21	D02271		10		D40623J		12		YC051-YC057
2514B	24	Y2	AN		10-5	34-58-21	D02271		10		D40623J		12		YC058
2514B	24	Y2	AN		8-3	34-58-21	D02271		10		D40623J		12		YC059-YN260
2514B	24	Y2	AN		8-2	34-58-21	D02271		10		D40623J		12		YN501-YR328
2514R	24	Y2	AN		0-0	34-58-21	D02271		7		D40623J		11		ALL
2514Z			AN		0-0	34-58-21	D02271	DED			D40623J	S/R			ALL
2515B	24	Y2	AP		10-1	23-32-21	D10193		6		D40625J		7		YC051-YC057
2515B	24	Y2	AP		10-3	23-32-21	D10193		6		D40625J		7		YC058
2515B	24	Y2	AP		10-5	23-32-21	D40625J		7		D02879		21		YC059-YD157
2515R	24	Y2	AP		0-0	23-32-21	D10193		5		D40625J		6		YC051-YC058
2515R	24	Y2	AP		0-0	23-32-21	D40625J		6		D02879		40		YC059-YD157
2515Z			AP		0-0	23-32-21	D10193	DED			D40625J	S/R			YC051-YC058
2515Z			AP		0-0	23-32-21	D40625J	S/R			D02879	DED			YC059-YD157

WIRE LIST

D280A108

91-21-11

Section W0040

Page 33

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity			
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice	
W0041	286A0041			P61 - DATA LOADER CONTROL PANEL (continued)												
2516B	24	Y2	AQ		10-3	23-27-11	D02879		6		D40625J	25			YC051-YC057	
2516B	24	Y2	AQ		10-4	23-27-11	D02879		6		D40625J	25			YC058	
2516B	24	Y2	AQ		10-6	23-27-11	D02877		20		D40625J	25			YC059-YD157	
2516B	24	Y2	AQ		10-3	23-27-39	D02877		20		D40625J	25			YD158-YD170	
2516B	24	Y2	AQ		9-8	23-27-39	D02877		20		D40625J	25			YL951-YN260	
2516B	24	Y2	AQ		9-9	23-27-39	D02877		20		D40625J	25			YN501-YR328	
2516R	24	Y2	AQ		0-0	23-27-11	D02879		4		D40625J	24			YC051-YC058	
2516R	24	Y2	AQ		0-0	23-27-11	D02877		39		D40625J	24			YC059-YD157	
2516R	24	Y2	AQ		0-0	23-27-39	D02877		39		D40625J	24			YD158-YR328	
2516Z			AQ		0-0	23-27-11	D02879		DED		D40625J	S/R			YC051-YC058	
2516Z			AQ		0-0	23-27-11	D02877		DED		D40625J	S/R			YC059-YD157	
2516Z			AQ		0-0	23-27-39	D02877		DED		D40625J	S/R			YD158-YR328	
2519B	22	X2	AT		10-3	49-62-11	D02879		20		D40625J	37			YC051-YC057	
2519B	22	X2	AT		10-4	49-62-11	D02879		20		D40625J	37			YC058	
2519B	22	X2	AT		10-5	49-62-11	D02879		45		D40625J	37			YC059-YD157	
2519B	22	X2	AT		10-2	49-62-11	D02879		45		D40625J	37			YD158-YD170	
2519B	22	X2	AT		9-7	49-62-11	D02879		45		D40625J	37			YL951-YN260	
2519B	22	X2	AT		9-9	49-62-11	D02879		45		D40625J	37			YN501-YR328	
2519R	22	X2	AT		0-0	49-62-11	D02879		19		D40625J	36			YC051-YC058	
2519R	22	X2	AT		0-0	49-62-11	D02879		44		D40625J	36			YC059-YR328	
2519Z			AT		0-0	49-62-11	D02879		DED		D40625J	S/R			ALL	
2520B	22	X2	AU		10-1	23-15-15	D10193		2		D40625J	39			YC051-YC057	
2520B	22	X2	AU		10-3	23-15-15	D10193		2		D40625J	39			YC058	
2520B	22	X2	AU		10-6	23-15-15	D02877		33		D40625J	39			YC059-YD157	
2520R	22	X2	AU		0-0	23-15-15	D10193		1		D40625J	38			YC051-YC058	
2520R	22	X2	AU		0-0	23-15-15	D02877		56		D40625J	38			YC059-YD157	
2520Z			AU		0-0	23-15-15	D10193		DED		D40625J	S/R			YC051-YC058	
2520Z			AU		0-0	23-15-15	D02877		DED		D40625J	S/R			YC059-YD157	
2521B	24	Y2	AV		2-10	23-27-39	D10901		9		SM00026		S		YL951-YL954, YN231-YN235	
2521B	22	X2	AV		6-7	31-32-15	D10901		9		D02875	9			YL955-YL999, YN236-YN260	
2521B	22	X2	AV		6-6	31-32-15	D10901		9		D02875	9			YN501-YR328	
2521R	24	Y2	AV		0-0	23-27-39	D10901		8		SM00025		S		YL951-YL954, YN231-YN235	
2521R	22	X2	AV		0-0	31-32-15	D10901		8		D02875	8			YL955-YL999, YN236-YR328	
2521Z			AV		0-0	23-27-39	D10901		DED		SM00027		S		YL951-YL954, YN231-YN235	

WIRE LIST

D280A108

91-21-11

Section W0040

Page 34

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W0041	286A0041			P61 - DATA LOADER CONTROL PANEL (continued)											
2521Z				AV	0-0	31-32-15	D10901		DED			D02875	DED		YL955-YL999, YN236-YR328
2522B	22		VG	AW	6-7	31-32-15	D10901		11			D02875	11		YL951-YL954, YN231-YN235
2522B	22		X2	AW	6-7	31-32-15	D10901		11			D02875	11		YL955-YL999, YN236-YN260
2522B	22		X2	AW	6-6	31-32-15	D10901		11			D02875	11		YN501-YR328
2522R	22		VG	AW	0-0	31-32-15	D10901		10			D02875	10		YL951-YL954, YN231-YN235
2522R	22		X2	AW	0-0	31-32-15	D10901		10			D02875	10		YL955-YL999, YN236-YR328
2522Z				AW	0-0	31-32-15	D10901		DED			D02875	DED		YL951-YR328
2523B	24		Y2	AX	6-9	23-27-39	D10901		2			D40625J	33		YL951-YL954, YN231-YN235
2523B	22		X2	AX	6-7	31-32-15	D10901		2			D02875	2		YL955-YL999, YN236-YN260
2523B	22		X2	AX	6-6	31-32-15	D10901		2			D02875	2		YN501-YR328
2523R	24		Y2	AX	0-0	23-27-39	D10901		1			D40625J	32		YL951-YL954, YN231-YN235
2523R	22		X2	AX	0-0	31-32-15	D10901		1			D02875	1		YL955-YL999, YN236-YR328
2523Z				AX	0-0	23-27-39	D10901		DED			D40625J	S/R		YL951-YL954, YN231-YN235
2523Z				AX	0-0	31-32-15	D10901		DED			D02875	DED		YL955-YL999, YN236-YR328
2525B	24		Y2	AZ	10-6	34-61-18	D02877		22			D40625J	43		YC059-YD157
2525B	24		Y2	AZ	10-3	34-61-18	D02877		22			D40625J	43		YD158-YD170
2525B	24		Y2	AZ	9-8	34-61-18	D02877		22			D40625J	43		YL951-YN260
2525B	24		Y2	AZ	9-9	34-61-18	D02877		22			D40625J	43		YN501-YR328
2525R	24		Y2	AZ	0-0	34-61-18	D02877		41			D40625J	42		YC059-YR328
2525Z				AZ	0-0	34-61-18	D02877		DED			D40625J	S/R		YC059-YR328
2526B	24		Y2	BA	10-5	34-61-18	D02879		47			D40625J	46		YC059-YD157
2526B	24		Y2	BA	10-2	34-61-18	D02879		47			D40625J	46		YD158-YD170
2526B	24		Y2	BA	9-7	34-61-18	D02879		47			D40625J	46		YL951-YN260
2526B	24		Y2	BA	9-9	34-61-18	D02879		47			D40625J	46		YN501-YR328
2526R	24		Y2	BA	0-0	34-61-18	D02879		46			D40625J	45		YC059-YR328
2526Z				BA	0-0	34-61-18	D02879		DED			D40625J	S/R		YC059-YR328
2527B	24		Y2	BB	10-0	34-61-18	D10193		41			D40623J	20		YC059-YN260
2527B	24		Y2	BB	9-9	34-61-18	D10193		41			D40623J	20		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0040

Page 35

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0041	286A0041			P61 - DATA LOADER CONTROL PANEL (continued)											
2527R	24	Y2	BB		0-0	34-61-18	D10193	42			D40623J	19			YC059-YR328
2527Z			BB		0-0	34-61-18	D10193	DED			D40623J	S/R			YC059-YR328
2529B	24	Y2	BD		10-6	34-61-26	D02877	21			D40625J	14			YC059-YD157
2529B	24	Y2	BD		10-3	34-61-26	D02877	21			D40625J	14			YD158-YD170
2529B	24	Y2	BD		9-8	34-61-26	D02877	21			D40625J	14			YL951-YN260
2529B	24	Y2	BD		9-9	34-61-26	D02877	21			D40625J	14			YN501-YR328
2529R	24	Y2	BD		0-0	34-61-26	D02877	40			D40625J	13			YC059-YR328
2529Z			BD		0-0	34-61-26	D02877	DED			D40625J	S/R			YC059-YR328
2530B	24	Y2	BE		10-0	34-61-26	D10193	40			D40623J	25			YC059-YN260
2530B	24	Y2	BE		9-9	34-61-26	D10193	40			D40623J	25			YN501-YR328
2530R	24	Y2	BE		0-0	34-61-26	D10193	21			D40623J	24			YC059-YR328
2530Z			BE		0-0	34-61-26	D10193	DED			D40623J	S/R			YC059-YR328
2531B	24	Y2	BF		10-6	22-11-53	D02877	32			D40625J	48			YC059-YD157
2531B	24	Y2	BF		10-3	22-11-53	D02877	32			D40625J	48			YD158-YD170
2531B	24	Y2	BF		9-8	22-11-53	D02877	32			D40625J	48			YL951-YN260
2531B	24	Y2	BF		9-9	22-11-53	D02877	32			D40625J	48			YN501-YR328
2531R	24	Y2	BF		0-0	22-11-53	D02877	55			D40625J	47			YC059-YR328
2531Z			BF		0-0	22-11-53	D02877	DED			D40625J	S/R			YC059-YR328
2532B	24	Y2	BG		10-0	22-11-53	D10193	55			D40623J	27			YC059-YN260
2532B	24	Y2	BG		9-9	22-11-53	D10193	55			D40623J	27			YN501-YR328
2532R	24	Y2	BG		0-0	22-11-53	D10193	54			D40623J	26			YC059-YR328
2532Z			BG		0-0	22-11-53	D10193	DED			D40623J	S/R			YC059-YR328
2533B	22	X2	BH		5-5	31-32-15	SP00845		S		D40625J	10			YN501-YR301
2533B	22	X2	BH		4-3	31-32-15	TB0610Y	B021	1A		D40625J	10			YR303-YR328
2533R	22	X2	BH		0-0	31-32-15	SP00843		S		D40625J	9			YN501-YR301
2533R	22	X2	BH		0-0	31-32-15	TB0610Y	A021	1A		D40625J	9			YR303-YR328
2533Z			BH		0-0	31-32-15	SP00847		S		D40625J	S/R			YN501-YR301
2533Z			BH		0-0	31-32-15	GB00610	ST..	1A		D40625J	S/R			YR303-YR328
2535B	24	Y2	BJ		3-9	23-27-39	D02875	9			SM00026		S		YL951-YL954, YN231-YN235
2535R	24	Y2	BJ		0-0	23-27-39	D02875	8			SM00025		S		YL951-YL954, YN231-YN235
2535Z			BJ		0-0	23-27-39	D02875	DED			SM00027		S		YL951-YL954, YN231-YN235
2536B	24	Y2	BK		9-7	23-27-39	D02875	2			D40625J	12			YL951-YL954, YN231-YN235
2536R	24	Y2	BK		0-0	23-27-39	D02875	1			D40625J	11			YL951-YL954, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W0040

Page 36

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice
W0041	286A0041				P61 - DATA LOADER CONTROL PANEL (continued)										
2536Z				BK	0-0	23-27-39	D02875		DED		D40625J	S/R			YL951-YL954, YN231-YN235
2537B	24	Y2	BL		6-4	23-27-39	D40625J		54		SM00026		S		YL951-YL954, YN231-YN235
2537R	24	Y2	BL		0-0	23-27-39	D40625J		53		SM00025		S		YL951-YL954, YN231-YN235
2537Z			BL		0-0	23-27-39	D40625J		S/R		SM00027		S		YL951-YL954, YN231-YN235
3001B	24	PM	GA		7-3	23-51-31	D04151J		6		SM00006		S		YC051-YC057
3001B	24	PM	GA		6-5	23-51-31	D04151J		6		SM00006		S		YC058-YN260
3001B	24	PM	GA		7-0	23-51-31	D04151J		6		SM00006		S		YN501-YR328
3001R	24	PM	GA		0-0	23-51-31	D04151J		5		SM00005		S		ALL
3001Y	24	PM	GA		0-0	23-51-31	D04151J		7		SM00007		S		ALL
3002B	24	PM	GB		6-5	23-51-31	D04151J		10		SM00012		S		YD158-YN260
3002B	24	PM	GB		7-0	23-51-31	D04151J		10		SM00012		S		YN501-YR328
3002R	24	PM	GB		0-0	23-51-31	D04151J		9		SM00011		S		YD158-YR328
3002Y	24	PM	GB		0-0	23-51-31	D04151J		8		SM00013		S		YD158-YR328
A-AA			VA		0-0	23-51-31	D06035		BLK		SM00001		S		ALL
A-AB			VA		0-0	23-51-31	D06035		BLU		SM00002		S		ALL
B-BA			VB		0-0	23-51-31	D06045		RED		SM00005		S		ALL
B-BB			VB		0-0	23-51-31	D06045		BLK		SM00006		S		ALL
B-BC			VB		0-0	23-51-31	D06045		BLU		SM00007		S		ALL
C-CA			VC		0-0	23-51-31	D06069		RED		SM00011		S		YD158-YR328
C-CB			VC		0-0	23-51-31	D06069		BLK		SM00012		S		YD158-YR328
C-CC			VC		0-0	23-51-31	D06069		BLU		SM00013		S		YD158-YR328
FRAA					0-0	34-61-18	D01907			AB	D01907	16			YC051-YC058
FRAA					0-0	31-32-15	D01907			AB	D01907	16			YC059-YR328
FRAC					0-0	34-61-18	D01907			AC	D01907	5			YC051-YC058
FRAC					0-0	31-32-15	D01907			AC	D01907	5			YC059-YR328
W0044	286A0044				P6 (LOAD WIRES)										
0001	20	CQ			7-5	24-11-11	C01283		=L	D	D40352J	4			ALL
0002	18	CQ			7-8	24-11-11	C01286		=L	D	D40550J	13	18		YC051-YC058
0002	18	CQ			7-7	24-11-11	C01286		=L	D	D40550J	13	18		YC059-YR328
0003	20	CQ			7-6	24-11-21	C01284		=L	D	D40352J	6			ALL
0004	18	CQ			7-7	24-11-21	C01287		=L	D	D40558J	10	18		YC051-YC058
0004	18	CQ			7-6	24-11-21	C01287		=L	D	D40558J	10	18		YC059-YR328
0005	20	CQ			7-7	24-22-31	C01285		=L	D	D40352J	8			ALL

WIRE LIST

D280A108

91-21-11

Section W0040

Page 37

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0044	286A0044			P6 (LOAD WIRES) (continued)											
0007	22		PA		11-2	24-23-51	D40386J	14			D40226J	1			YC051-YC057, YC059-YR328
0007	22		PA		12-2	24-23-51	D40386J	14			D40226J	1			YC058
0008	22		PA		4-7	24-23-51	C01328	=L	D		SM00037		9		ALL
0009	22		PA		3-6	24-23-51	D40368J	1			SM00037		9		ALL
0010	22		PA		1-11	24-23-51	D11756	X1			SM00037		9		ALL
0011	22		PA		4-4	24-23-51	D11756	X2			D40386J	16			ALL
0012	22		PA		3-2	24-23-51	D40396J	9			SM00037		9		ALL
0013	22		PA		6-2	24-28-11	C00072	=L	D		SM00043		9		YC051-YC057
0013	22		PA		6-1	24-28-11	C00072	=L	D		SM00043		9		YC058-YR328
0014	22		PA		6-7	24-28-11	D11714B	26			D40536J	11			ALL
0018	24		B6		4-2	24-31-11	D11712B	19			D00944	C1			ALL
0019	24		B6		1-11	24-31-11	D11712B	1			SM00038		9		ALL
0020	24		B6		4-6	24-31-11	D40550J	35			SM00038		9		ALL
0021	24		B6		4-8	24-31-11	D40352J	13			SM00038		9		ALL
0022	24		B6		2-8	24-31-11	D00944	C2			GD00620	DC..	1A		ALL
0023	24		PK		7-11	24-32-11	C01397	=L	D	*	D40368J	3			ALL
0024	24		PK		7-7	24-32-11	C01397	=L	D	*	D40396J	2			ALL
0025	24		PK		5-2	24-32-11	D11714B	65			D40368J	2			ALL
0026	08		CQ		5-1	24-32-11	D11712B	A3			TB5060G	8	E		ALL
0027	24		PK		6-9	24-32-11	D11714B	50			D40550J	39			ALL
0028	20		PA		5-2	24-32-11	D11714B	42			D40368J	4			ALL
0029	24		PK		5-4	24-32-11	D11712B	5			D40396J	8			ALL
0030	20		PA		4-10	24-32-11	D11714B	24			D40396J	3			ALL
0031	18		PA		7-7	25-29-11	C01643	=L	D		D40750J	31	18		YL951-YL999, YN232-YR328
0032	24		B6		8-1	24-33-11	C00026	=L	D		D40550J	53			YC051-YC058
0032	24		B6		8-0	24-33-11	C00026	=L	D		D40550J	53			YC059-YR328
0033	24		B6		8-5	24-33-11	C00134	=L	D		D40550J	55			YC051-YC058
0033	24		B6		8-4	24-33-11	C00134	=L	D		D40550J	55			YC059-YR328
0034	24		PK		8-3	24-33-11	C00023	=L	D		D40550J	46			YC051-YC058
0034	24		PK		8-2	24-33-11	C00023	=L	D		D40550J	46			YC059-YR328
0035	24		PK		8-4	24-33-11	C01338	=L	D		D40550J	36			YC051-YC058
0035	24		PK		8-3	24-33-11	C01338	=L	D		D40550J	36			YC059-YR328
0036	24		PK		6-4	24-33-11	D11712B	7			D40550J	54			ALL
0037	12		CQ		3-11	24-34-11	D11712A	1			TB5060B	8	E		ALL
0038	24		B6		5-5	24-34-11	D11714A	10			D40800J	26			ALL
0039	08		CQ		5-6	24-34-11	D11712B	A7			TB5060H	4	E		ALL
0040	24		B6		6-10	24-34-11	D11714A	13			D40550J	47			ALL

WIRE LIST

D280A108

91-21-11

Section W0040

Page 38

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0044		286A0044			P6 (LOAD WIRES) (continued)											
0041		24		B6		6-10	24-34-11	D11714A	12			D40550J	48			ALL
0042		24		B6		6-10	24-34-11	D11714A	25			D40550J	30			ALL
0043		24		B6		6-10	24-34-11	D11714A	14			D40550J	49			ALL
0044		20		CQ		7-6	24-34-11	D11714B	22			C02029	=L	D		ALL
0047		22		PA		4-5	24-41-11	D00944	X1			D40352J	5			ALL
0048		20		CQ		7-8	24-41-11	C01290	=L	D		D40352J	23			ALL
0049		22		PA		1-10	24-41-11	D40654J	4			D40396J	1			ALL
0050		24		B6		8-6	31-22-11	C00736	=L	D		D46052J	1			ALL
0051		24		B6		8-5	31-22-11	C00737	=L	D		D46052J	2			ALL
0052		22		CQ		9-2	31-51-11	C00451	=L	D		D40822J	3			ALL
0053		20		CQ		7-8	31-52-11	C00131	=L	D		D01598	8			ALL
0054		20		CQ		7-7	31-52-11	C00132	=L	D		D01598	2			ALL
0055		20		CQ		5-1	31-52-11	D01598	6			D46052J	16			ALL
0056		20		CQ		6-0	31-52-11	D01618	C3			D40822J	7			ALL
0057		20		CQ		7-6	31-52-21	C01276	=L	D		D40550J	11			YC051-YC058
0057		20		CQ		7-5	31-52-21	C01276	=L	D		D40550J	11			YC059-YR328
0058		20		CQ		7-6	31-52-25	C01275	=L	D		D40550J	7			YC051-YC058
0058		20		CQ		7-4	31-52-25	C01275	=L	D		D40550J	7			YC059-YR328
0059		20		CQ		7-7	31-52-51	C01277	=L	D		D40550J	10			YC051-YC058
0059		20		CQ		7-6	31-52-51	C01277	=L	D		D40550J	10			YC059-YR328
0061		22		PA		9-1	34-51-21	C01375	=L	D		D46061J	2			ALL
0062		22		PA		9-3	34-51-21	C01379	=L	D		D46061J	3			ALL
0063		20		CQ		7-8	31-52-75	C01278	=L	D		D40550J	4			YC051-YC058
0063		20		CQ		7-7	31-52-75	C01278	=L	D		D40550J	4			YC059-YR328
0064		16		PA		8-4	33-11-11	C00331	=L	D		D46052J	23			ALL
0065		16		PA		8-4	33-11-21	C00335	=L	D		D46065J	17	16		ALL
0066		16		CQ		7-11	33-11-32	C00701	=L	D		D46052J	21			ALL
0068		20		CQ		7-9	33-11-33	C00701	=L	D		D40816J	3			ALL
0069		16		PA		8-3	33-11-33	C00284	=L	D		D40816J	4			ALL
0070		18		PA		7-0	33-12-11	C00328	=L	D		D40532J	1	18		YC051-YC058
0070		18		PA		6-11	33-12-11	C00328	=L	D		D40532J	1	18		YC059-YR328
0071		18		PA		7-0	33-12-11	C00323	=L	D		D40532J	21	18		YC051-YC058
0071		18		PA		6-11	33-12-11	C00323	=L	D		D40532J	21	18		YC059-YR323, YR325-YR328
0072		10		PA		6-4	33-12-11	C00325	=B	D		TB5060B	1	E		YC051-YC057
0072		10		PA		6-3	33-12-11	C00325	=B	D		TB5060B	1	E		YC058-YR328
0073		10		PA		4-3	33-12-11	C00325	=L	D		T00033	HV	E		ALL
0074		10		PA		1-6	33-12-11	T00033	G	E		GD00608	AC..	E		ALL
0075		10		PA		4-3	33-12-11	C00328	=B	D	*	T00033	LV1	E		ALL

WIRE LIST

D280A108

91-21-11

Section W0040

Page 39

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0044	286A0044			P6 (LOAD WIRES) (continued)											
0076	18	PA			6-11	33-12-11	C00326	=L	D		D40532J	3	18		YC051-YC058
0076	18	PA			6-10	33-12-11	C00326	=L	D		D40532J	3	18		YC059-YR328
0077	18	PA			7-0	33-12-11	C00329	=L	D		D40532J	2	18		YC051-YC058
0077	18	PA			6-10	33-12-11	C00329	=L	D		D40532J	2	18		YC059-YR328
0078	10	PA			0-9	33-12-11	C00329	=B	D	*	C00328	=B	D	*	ALL
0079	10	PA			0-9	33-12-11	C00329	=B	D	*	C00326	=B	D		ALL
0080	10	PA			0-9	33-12-12	C00330	=B	D	*	C00390	=B	D	*	ALL
0081	10	PA			3-10	33-12-12	C00330	=B	D	*	T00034	LV1	E		ALL
0082	18	PA			6-4	33-12-12	C00330	=L	D		D40536J	15	18		YC051-YC058
0082	18	PA			6-2	33-12-12	C00330	=L	D		D40536J	15	18		YC059-YR328
0083	10	PA			4-5	33-12-12	C00325	=L	D		T00034	HV	E		ALL
0084	10	PA			1-9	33-12-12	T00034	G	E		GD00608	AC..	E		ALL
0085	10	PA			0-10	33-12-12	C00327	=B	D		C00390	=B	D	*	ALL
0086	18	PA			6-3	33-12-12	C00327	=L	D		D40536J	14	18		YC051-YC058
0086	18	PA			6-2	33-12-12	C00327	=L	D		D40536J	14	18		YC059-YR328
0087	18	PA			6-4	33-12-12	C00390	=L	D		D40536J	27	18		YC051-YC058
0087	18	PA			6-3	33-12-12	C00390	=L	D		D40536J	27	18		YC059-YR328
0089	20	PA			8-7	33-14-11	C00751	=L	D		D46065J	18			ALL
0090	18	PA			8-4	33-14-12	C00283	=L	D		D40816J	1	18		ALL
0091	18	PA			8-11	33-14-12	D40816J	10			D40536J	1	18		ALL
0092	20	CQ			8-0	33-14-12	C00282	=L	D		D40550J	21			YC051-YC058
0092	20	CQ			7-11	33-14-12	C00282	=L	D		D40550J	21			YC059-YR328
0093	20	CQ			2-0	33-14-12	D40744J	=1	VY		D40550J	52			ALL
0095	18	PA			7-2	33-14-12	C00219	=L	D		D40536J	29	18		YC051-YC058
0095	18	PA			7-1	33-14-12	C00219	=L	D		D40536J	29	18		YC059-YR328
0097	20	CQ			7-11	33-14-12	C00161	=L	D		D40550J	3			YC051-YC058
0097	20	CQ			7-10	33-14-12	C00161	=L	D		D40550J	3			YC059-YR328
0098	20	PA			3-5	33-17-11	C00308	=L	D		SM00025		9		ALL
0099	20	PA			4-1	33-17-11	SM00025		9		D40582J	4			YC051-YC058
0099	20	PA			4-0	33-17-11	SM00025		9		D40582J	4			YC059-YR328
0100	20	PA			4-2	33-17-11	SM00025		9		D40512J	14			YC051-YC058
0100	20	PA			4-1	33-17-11	SM00025		9		D40512J	14			YC059-YR328
0101	20	PA			9-10	33-17-11	D40218J		9		C00309	=L	D	*	YC051-YC057
0101	20	PA			9-9	33-17-11	D40218J		9		C00309	=L	D	*	YC058-YR328
0102	20	PA			6-11	33-17-11	C00309	=L	D	*	TB5060J	1	E		YC051-YC057
0102	20	PA			6-10	33-17-11	C00309	=L	D	*	TB5060J	1	E		YC058-YR328
0104	20	CQ			4-9	33-18-11	C00133	=L	D		SM00018		9		ALL
0105	20	CQ			2-6	33-18-11	SM00018		9		D01598	29			ALL
0106	20	CQ			2-0	33-18-11	D01598		27		SM00019		9		ALL

WIRE LIST

D280A108

91-21-11

Section W0040

Page 40

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W0044	286A0044	P6 (LOAD WIRES) (continued)			
0107	20 CQ	3-0 33-18-11	D01598 7	SM00045 9	YC051-YC057
0107	20 CQ	2-11 33-18-11	D01598 7	SM00045 9	YC058-YR328
0108	20 CQ	2-0 33-18-11	D01598 5	SM00019 9	ALL
0109	20 CQ	1-4 33-18-11	D10762 X1	D01618 D1	ALL
0110	20 CQ	2-10 33-18-11	D10762 X2	GD00626 DC.. 1A	YC051-YR323, YR325-YR328
0111	20 CQ	2-5 33-18-11	D01614 A2	GD00626 DC.. 1A	YC051-YR323, YR325-YR328
0112	20 CQ	2-4 33-18-11	SM00018 9	D01614 D2	ALL
0113	20 CQ	2-5 33-18-11	D01614 C2	GD00626 DC.. 1A	YC051-YR323, YR325-YR328
0114	20 CQ	2-5 33-18-11	D01614 B2	GD00626 DC.. 1A	YC051-YR323, YR325-YR328
0115	20 CQ	2-4 33-18-11	SM00018 9	D01614 X1	ALL
0116	20 CQ	2-10 33-18-11	D01614 X2	SM00053 9	YC051-YC057
0116	20 CQ	2-9 33-18-11	D01614 X2	SM00053 9	YC058-YR328
0117	20 CQ	2-7 33-18-11	SM00045 9	D46052J 3	YC051-YC057
0117	20 CQ	2-8 33-18-11	SM00045 9	D46052J 3	YC058-YR328
0118	20 CQ	2-1 33-18-11	D01616 X1	SM00021 9	ALL
0119	20 CQ	2-1 33-18-11	SM00019 9	D01616 X2	ALL
0120	20 CQ	2-8 33-18-11	D01616 D2	GD00626 DC.. 1A	YC051-YR323, YR325-YR328
0121	20 CQ	5-4 33-18-11	D01616 D3	SM00014 9	ALL
0122	20 CQ	2-11 33-18-11	SM00014 9	M00207 =C \$	YC051-YC052
0123	20 CQ	8-0 33-18-11	M00207 =A F	GD00626 DC.. 1A	YC051-YC057
0123	20 CQ	7-11 33-18-11	M00207 =A F	GD00626 DC.. 1A	YC058-YR323, YR325-YR328
0124	20 CQ	1-11 33-18-11	SM00021 9	D01618 D2	ALL
0125	20 CQ	1-11 33-18-11	SM00021 9	D01618 X1	ALL
0126	20 CQ	1-11 33-18-11	SM00019 9	D01618 X2	ALL
0127	20 CQ	1-7 33-18-11	D01618 C2	GD00620 DC.. 1A	ALL
0128	20 PA	5-0 33-18-11	C00312 =L D	SM00024 9	ALL
0129	20 PA	4-11 33-18-11	C00311 =L D	SM00023 9	ALL
0130	20 CQ	4-10 33-18-11	C00310 =L D	SM00022 9	ALL
0131	20 CQ	1-0 33-18-11	C00313 =B D	C00314 =B D	ALL
0132	20 CQ	1-0 33-18-11	C00315 =B D	C00316 =B D	ALL
0133	20 CQ	1-0 33-18-11	C00317 =B D	C00318 =B D	ALL
0134	20 CQ	4-5 33-18-11	C00317 =B D	M00208 =A F	YC051-YC057
0134	20 CQ	4-4 33-18-11	C00317 =B D	M00208 =A F	YC058-YR328

WIRE LIST

D280A108

91-21-11

Section W0040

Page 41

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0044	286A0044				P6 (LOAD WIRES) (continued)										
0135	20		CQ		6-0	33-18-11	C00315	=B	D	*	M00209	=A	F	*	YC051-YC057
0135	20		CQ		5-5	33-18-11	C00315	=B	D	*	M00209	=A	F	*	YC058-YR328
0136	20		CQ		4-5	33-18-11	M00210	=A	F	*	C00313	=B	D	*	YC051-YC057
0136	20		CQ		4-7	33-18-11	M00210	=A	F	*	C00313	=B	D	*	YC058-YR328
0137	20		PA		2-6	33-18-11	SM00024		9		D01598	36			ALL
0138	20		PA		2-6	33-18-11	SM00023		9		D01598	34			ALL
0139	20		CQ		2-6	33-18-11	SM00022		9		D01598	28			ALL
0140	20		CQ		2-0	33-18-11	SM00020		9		D01598	26			ALL
0141	20		CQ		2-0	33-18-11	SM00026		9		D01598	32			ALL
0142	20		CQ		2-0	33-18-11	SM00027		9		D01598	30			ALL
0143	20		CQ		6-3	33-18-11	M00208	=C	\$		SM00020		9		YC051-YC052
0144	20		CQ		6-8	33-18-11	M00209	=C	\$		SM00026		9		YC051-YC052
0145	20		CQ		5-3	33-18-11	M00210	=C	\$		SM00027		9		YC051-YC052
0146	20		CQ		7-9	33-18-11	M00208	=A	F	*	D01616	C3			ALL
0147	20		CQ		2-1	33-18-11	SM00020		9		D01616	C2			ALL
0148	20		CQ		8-3	33-18-11	M00209	=A	F	*	D01616	B3			YC051-YC057
0148	20		CQ		8-1	33-18-11	M00209	=A	F	*	D01616	B3			YC058-YR328
0149	20		CQ		2-1	33-18-11	SM00026		9		D01616	B2			ALL
0150	20		CQ		7-3	33-18-11	M00210	=A	F	*	D01616	A3			YC051-YC057
0150	20		CQ		7-5	33-18-11	M00210	=A	F	*	D01616	A3			YC058-YR328
0151	20		CQ		2-1	33-18-11	SM00027		9		D01616	A2			ALL
0152	20		CQ		6-2	33-18-21	C00314	=L	D		SM00013		9		YC051-YC057
0152	20		CQ		6-1	33-18-21	C00314	=L	D		SM00013		9		YC058-YR328
0153	20		CQ		2-7	33-18-21	SM00013		9		D46052J	5			YC051-YC057
0153	20		CQ		2-8	33-18-21	SM00013		9		D46052J	5			YC058-YR328
0154	20		CQ		2-6	33-18-21	D01614		C1		SM00009		9		ALL
0155	20		CQ		3-8	33-18-21	SM00009		9		D46052J	6			ALL
0156	20		CQ		2-6	33-18-21	D01614		B1		SM00012		9		ALL
0157	20		CQ		3-8	33-18-21	SM00012		9		D46052J	7			ALL
0158	20		PA		4-5	33-18-21	D01618		A2		SM00036		9		ALL
0159	20		PA		2-6	33-18-21	D01618		A3		SM00017		9		ALL
0160	20		PA		6-7	33-18-21	SM00017		9		M00394	=A	E		YC051-YC057
0160	20		PA		6-6	33-18-21	SM00017		9		M00394	=A	E		YC058-YR328
0161	20		PA		3-4	33-18-21	SM00017		9		D46065J	20			ALL
0162	20		CQ		2-7	33-18-62	SM00045		9		D46052J	10			YC051-YC057
0162	20		CQ		2-8	33-18-62	SM00045		9		D46052J	10			YC058-YR328
0164	20		CQ		2-4	33-18-22	C00318	=L	D		SM00008		9		ALL
0165	20		CQ		5-5	33-18-22	SM00008		9		D46052J	15			ALL
0167	20		CQ		5-1	33-18-23	C00317	=L	D		SM00007		9		YC051-YC057

WIRE LIST

D280A108

91-21-11

Section W0040

Page 42

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0044		286A0044			P6 (LOAD WIRES) (continued)											
0167		20		CQ		5-0	33-18-23	C00317	=L	D		SM00007		9		YC058-YR328
0168		20		CQ		2-7	33-18-23	SM00007		9		D46052J		8		YC051-YC057
0168		20		CQ		2-8	33-18-23	SM00007		9		D46052J		8		YC058-YR328
0169		20		CQ		7-5	33-18-31	C00316	=L	D		D40550J		24		YC051-YC058
0169		20		CQ		7-3	33-18-31	C00316	=L	D		D40550J		24		YC059-YR328
0170		20		CQ		2-6	33-18-31	D01614	A1			SM00011		9		ALL
0171		20		CQ		6-1	33-18-31	SM00011		9		D40550J		16		ALL
0172		20		CQ		2-10	33-18-32	C00313	=L	D		SM00040		9		ALL
0173		20		CQ		5-0	33-18-32	SM00008		9		D40550J		31		YC051-YC058
0173		20		CQ		4-11	33-18-32	SM00008		9		D40550J		31		YC059-YR328
0174		20		CQ		6-1	33-18-32	SM00009		9		D40550J		33		ALL
0175		20		CQ		6-10	33-18-33	C01180	=L	D	*	D40550J		15		YC051-YC058
0175		20		CQ		6-9	33-18-33	C01180	=L	D	*	D40550J		15		YC059-YR328
0176		20		CQ		6-9	33-18-33	C01179	=L	D	*	D40550J		17		YC051-YC058
0176		20		CQ		6-8	33-18-33	C01179	=L	D	*	D40550J		17		YC059-YR328
0177		20		CQ		7-3	33-18-34	SM00007		9		D40550J		8		YC051-YC057
0177		20		CQ		7-2	33-18-34	SM00007		9		D40550J		8		YC058-YR328
0178		20		CQ		6-10	33-18-35	C01180	=L	D	*	D40550J		50		YC051-YC058
0178		20		CQ		6-9	33-18-35	C01180	=L	D	*	D40550J		50		YC059-YR328
0179		20		CQ		8-4	33-18-36	D01598		12		D40550J		32		ALL
0180		20		CQ		8-4	33-18-36	D01598		16		D40550J		23		ALL
0181		20		CQ		3-2	33-18-36	D01598		20		GD00620	DC..	1A		ALL
0182		20		CQ		2-6	33-18-36	D01614	D1			SM00010		9		ALL
0183		20		CQ		6-1	33-18-36	SM00010		9		D40550J		5		ALL
0184		20		CQ		4-2	33-18-37	SM00014		9		D40550J		43		YC051-YC058
0184		20		CQ		4-1	33-18-37	SM00014		9		D40550J		43		YC059-YR328
0185		20		CQ		7-2	33-18-37	C00133	=L	D		D40550J		2		YC051-YC058
0185		20		CQ		7-1	33-18-37	C00133	=L	D		D40550J		2		YC059-YR328
0186		20		CQ		6-1	33-18-41	SM00012		9		D40550J		41		ALL
0187		20		CQ		3-9	33-18-41	SM00011		9		TB5060B		7	E	ALL
0188		20		CQ		4-2	33-18-51	SM00010		9		D40822J		1		ALL
0189		20		CQ		6-0	33-18-51	D01618	D3			D40822J		2		ALL
0190		20		CQ		8-9	33-18-61	C00315	=L	D	*	D40822J		8		ALL
0191		20		CQ		3-0	33-18-61	SM00013		9		D40822J		9		YC051-YC057
0191		20		CQ		3-1	33-18-61	SM00013		9		D40822J		9		YC058-YR328
0192		20		CQ		4-2	33-18-61	SM00012		9		D40822J		10		ALL
0193		20		CQ		4-2	33-18-61	SM00009		9		D40822J		11		ALL
0194		20		CQ		6-11	33-18-61	SM00014		9		D40800J		6		YC051-YD154
0194		20		CQ		6-11	33-18-63	SM00014		9		D40800J		6		YD155-YR328

WIRE LIST

D280A108

91-21-11

Section W0040

Page 43

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0044	286A0044				P6 (LOAD WIRES) (continued)										
0195	20		CQ		5-4	33-18-62	D10046		7		C01179	=B	D		ALL
0196	20		PA		1-6	33-18-62	D10046		1		SM00023		9		ALL
0197	20		CQ		1-6	33-18-62	D10046		2		SM00022		9		ALL
0198	20		PA		1-6	33-18-62	D10046		3		SM00024		9		ALL
0199	20		CQ		5-5	33-18-62	D10046		8		C01180	=B	D		ALL
0200	20		CQ		4-6	33-18-62	D10046		11		D40822J		20		ALL
0201	20		CQ		1-6	33-18-62	D10046		5		SM00018		9		ALL
0202	20		CQ		2-0	33-18-62	D10046		4		SM00045		9		YC051-YC057
0202	20		CQ		1-11	33-18-62	D10046		4		SM00045		9		YC058-YR328
0203	20		CQ		4-0	33-18-62	D10046		6		D46052J		13		ALL
0204	20		CQ		6-1	33-18-63	SM00040			9	D40800J		7		ALL
0205	20		CQ		2-7	33-18-63	SM00007			9	D40812J		4		YC051-YC057
0205	20		CQ		2-8	33-18-63	SM00007			9	D40812J		4		YC058-YR328
0206	20		CQ		3-8	33-18-63	D40812J			5	SM00011			9	ALL
0207	22		CQ		10-11	29-25-11	C01085	=L	D		D40820J		7		ALL
0208	22		CQ		10-10	29-25-11	C01081	=L	D		D40820J		8		ALL
0209	22		CQ		10-8	29-23-11	C00781	=L	D		D40820J		2		YC051-YC057
0209	22		CQ		10-7	29-23-11	C00781	=L	D		D40820J		2		YC058-YR328
0210	22		PA		10-10	29-23-11	C00799	=L	D		D40800J		27		YC051-YC057
0210	22		PA		10-9	29-23-11	C00799	=L	D		D40800J		27		YC058-YR328
0211	18		PA		11-4	22-31-11	D40218J			39	D46065J		4		YC051-YC057, YC059-YD155
0211	18		PA		12-4	22-31-11	D40218J			39	D46065J		4		YC058
0212	22		PA		9-8	34-16-21	C00549	=L	D		D40822J		16		ALL
0213	20		PA		4-1	33-18-21	SM00036			9	M00394	=C	\$		YC051-YC057
0213	20		PA		4-0	33-18-21	SM00036			9	M00394	=C	\$		YC058-YR328
0221	20		PA		9-2	34-61-11	C01262	=L	D		D46067J		2		ALL
0223	20		PA		5-1	34-61-12	C01263	=L	D		D40536J		2		ALL
0224	24		PK		10-6	27-11-11	C00786	=L	D		D40820J		6		YC051-YC057
0224	24		PK		10-5	27-11-11	C00786	=L	D		D40820J		6		YC058-YR328
0225	24		PK		10-6	27-21-11	C00787	=L	D		D40820J		13		ALL
0226	20		CQ		6-1	27-23-11	C00362	=L	D		D40526J		5		YC051-YC058
0226	20		CQ		5-3	27-23-11	C00362	=L	D		D40526J		5		YC059-YR328
0227	20		PA		6-3	27-23-11	C00363	=L	D		D40526J		11		YC051-YC058
0227	20		PA		5-5	27-23-11	C00363	=L	D		D40526J		11		YC059-YR328
0228	20		PA		6-4	27-23-11	C01074	=L	D		D40502J		2		YC051-YC058
0228	20		PA		6-1	27-23-11	C01074	=L	D		D40502J		2		YC059-YR328
0229	20		PA		10-2	27-41-11	C00207	=L	D		D40820J		16		ALL
0230	20		PA		6-3	27-53-11	C00210	=L	D	*	D40502J		8		YC051-YC058

WIRE LIST

D280A108

91-21-11

Section W0040

Page 44

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0044		286A0044			P6 (LOAD WIRES) (continued)											
0230		20		PA		6-0	27-53-11	C00210	=L	D	*	D40502J	8			YC059-YR328
0231		16		PA		9-11	27-53-12	C00841	A2	D		D40574J	1			ALL
0232		16		PA		10-0	27-53-12	C00841	B2	D		D40574J	2			YC051-YC057
0232		16		PA		9-11	27-53-12	C00841	B2	D		D40574J	2			YC058-YR328
0233		16		PA		10-1	27-53-12	C00841	C2	D		D40574J	3			YC051-YC057
0233		16		PA		10-0	27-53-12	C00841	C2	D		D40574J	3			YC058-YR328
0234		22		CQ		10-3	27-54-11	C00566	=L	D		D40820J	9			YC051-YC057
0234		22		CQ		10-2	27-54-11	C00566	=L	D		D40820J	9			YC058-YR328
0235		20		PA		6-2	27-61-11	C00204	=L	D		D40526J	12			YC051-YC058
0235		20		PA		5-4	27-61-11	C00204	=L	D		D40526J	12			YC059-YR328
0236		20		PA		4-10	27-62-11	C00440	=L	D		SM00036		9		YC051-YC057
0236		20		PA		4-9	27-62-11	C00440	=L	D		SM00036		9		YC058-YR328
0237		20		PA		5-4	27-62-11	D40820J	15			SM00036		9		ALL
0239		22		CQ		10-7	27-83-11	C01068	=L	D		D40368J	9			ALL
0240		20		CQ		11-2	29-11-11	C00347	=L	D		D40800J	3			YC051-YC057
0240		20		CQ		11-1	29-11-11	C00347	=L	D		D40800J	3			YC058-YR328
0241		20		CQ		10-10	29-11-11	C00348	=L	D		D40812J	3			ALL
0242		22		PA		6-4	29-11-11	C00779	=L	D		D40526J	13			YC051-YC058
0242		22		PA		6-1	29-11-11	C00779	=L	D		D40526J	13			YC059-YR328
0243		22		PA		7-0	29-11-11	C00780	=L	D		D40502J	9			YC051-YC058
0243		22		PA		6-8	29-11-11	C00780	=L	D		D40502J	9			YC059-YR328
0245		22		PA		9-9	34-57-21	C01383	=L	D		D46067J	3			ALL
0247		16		PA		9-4	23-12-21	C00166	=L	D	*	D46065J	6			YC051-YD157
0247		16		PA		9-4	23-12-21	C00166	=L	D		D46065J	6			YD158-YR328
0248		16		PA		9-4	23-12-21	C00166	=L	D	*	D46065J	8			YC051-YD157
0249		22		PA		8-1	31-53-11	C01398	=L	D		GD00624	DC..	1		YC051-YC057
0249		22		PA		8-3	31-53-11	C01398	=L	D		GD00624	DC..	1		YC058-YR328
0250		22		PA		9-5	31-53-11	C01398	=B	D		D40822J	6			ALL
0251		20		CQ		8-10	25-29-11	C00117	=L	D		D00154	=P	LD		YC051-YD153
0251		20		CQ		8-11	25-29-11	C00117	=L	D		D00154	=P	LD		YD154-YR328
0252		20		CQ		2-1	25-29-11	D00154	=N	LD		GD00638	DC..	1A		YC051-YD153
0252		20		CQ		2-2	25-29-11	D00154	=N	LD		GD00638	DC..	1A		YD154-YR328
0253		20		CQ		2-1	25-29-11	D00154	=G	LD		GD00638	ST..	1A		YC051-YD153
0253		20		CQ		2-2	25-29-11	D00154	=G	LD		GD00638	ST..	1A		YD154-YR328
0254		20		PA		7-5	25-29-11	D00150	=P	LD		D40396J	5			YC051-YD153
0254		20		PA		7-6	25-29-11	D00150	=P	LD		D40396J	5			YD154-YR328
0255		20		PA		2-2	25-29-11	D00150	=N	LD		GD00638	AC..	1A		YC051-YD153
0255		20		PA		2-3	25-29-11	D00150	=N	LD		GD00638	AC..	1A		YD154-YR328
0256		20		PA		2-2	25-29-11	D00150	=G	LD		GD00638	ST..	1A		YC051-YD153

WIRE LIST

D280A108

91-21-11

Section W0040

Page 45

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From			To			Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type
Wire No.														
W0044	286A0044	P6 (LOAD WIRES) (continued)												
0256	20	PA		2-3	25-29-11	D00150	=G	LD		GD00638	ST..	1A		YD154-YR328
0257	24	B6		8-11	32-31-11	C00129	=L	D		D46052J	29			ALL
0258	24	B6		8-9	32-31-11	C01356	=L	D		D40820J	19			ALL
0259	22	CQ		9-3	32-31-12	C01355	=L	D		D40750J	20			ALL
0260	22	PA		8-11	32-31-12	C01401	=L	D		D40750J	5			ALL
0261	22	PA		8-9	32-35-11	C01432	=L	D		D40800J	18			ALL
0262	24	PK		6-10	32-42-11	C00583	=L	D		TB0610Y	A001	1A		YC051-YC057
0262	24	PK		6-11	32-42-11	C00583	=L	D		TB0610Y	A001	1A		YC058-YD170
0262	24	PK		6-8	32-42-11	C00583	=L	D		TB0610Y	A001	1A		YL951-YR328
0264	24	PK		6-8	32-42-11	C01345	=L	D		TB0610Y	A003	1A		YC051-YC057
0264	24	PK		6-9	32-42-11	C01345	=L	D		TB0610Y	A003	1A		YC058-YD170
0264	24	PK		6-6	32-42-11	C01345	=L	D		TB0610Y	A003	1A		YL951-YR328
0266	24	PK		4-2	32-42-11	D46069J		9		TB0610Y	A001	1A		YC051-YC057
0266	24	PK		4-3	32-42-11	D46069J		9		TB0610Y	A001	1A		YC058-YD170
0266	24	PK		4-0	32-42-11	D46069J		9		TB0610Y	A001	1A		YL951-YR328
0268	24	PK		4-2	32-42-11	D46069J		11		TB0610Y	B001	1A		YC051-YC057
0268	24	PK		4-3	32-42-11	D46069J		11		TB0610Y	B001	1A		YC058-YD170
0268	24	PK		4-0	32-42-11	D46069J		11		TB0610Y	B001	1A		YL951-YR328
0269	24	PK		4-2	32-42-11	D46069J		12		TB0610Y	A003	1A		YC051-YC057
0269	24	PK		4-3	32-42-11	D46069J		12		TB0610Y	A003	1A		YC058-YD170
0269	24	PK		4-0	32-42-11	D46069J		12		TB0610Y	A003	1A		YL951-YR328
0270	24	PK		4-4	32-42-11	D46065J		16		TB0610Y	B003	1A		YC051-YC057
0270	24	PK		4-5	32-42-11	D46065J		16		TB0610Y	B003	1A		YC058-YD170
0270	24	PK		4-2	32-42-11	D46065J		16		TB0610Y	B003	1A		YL951-YR328
0271	24	PK		0-7	32-42-11	TB0610Y	B001	1A		TB0610Y	B003	1A		ALL
0272	24	PK		9-4	32-44-11	C01346	=L	D		D40822J	13			ALL
0273	22	PA		9-1	32-51-11	C01027	=L	D		D40750J	7			ALL
0274	24	B6		7-11	32-64-11	C01399	=L	D		D40820J	18			ALL
0275	22	CQ		8-4	32-64-12	C01400	=L	D		D40750J	8			ALL
0277	22	PA		9-8	34-33-21	C01385	=L	D		D46067J	5			ALL
0278	20	PA		9-5	34-41-11	C00120	=L	D		D40750J	4			YC051-YC052
0279	20	PA		8-8	34-53-21	C00188	=L	D		D46061J	8			ALL
0280	22	PA		9-6	34-53-31	C01194	=L	D		D40750J	1			ALL
0281	22	PA		9-2	34-55-21	C00192	=L	D		D46061J	9			ALL
0282	22	CQ		4-6	28-44-11	D00944		X2		D40386J	26			ALL
0283	22	PA		8-9	23-43-11	D40654J		5		D40536J	7			ALL
0284	22	PA		8-9	23-43-11	D40654J		6		D40536J	19			ALL
0285	22	PA		8-9	23-42-11	D40654J		7		D40536J	31			ALL
0286R	22	PH		10-11	26-12-11	C00388	=L	D		D46061J	11			YC051-YC057

WIRE LIST

D280A108

91-21-11

Section W0040

Page 46

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description		From			To						
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0044	286A0044			P6 (LOAD WIRES) (continued)											
0286R	22		PH		10-10	26-12-11	C00388	=L	D		D46061J	11			YC058-YR328
0287	24		PK		10-3	27-28-11	C00788	=L	D		D46065J	22			ALL
0288	24		PK		10-5	27-52-11	C00213	=L	D		D46061J	14			YC051-YC057
0288	24		PK		10-4	27-52-11	C00213	=L	D		D46061J	14			YC058-YR328
0289	18		CQ		9-5	22-11-11	C01630	=L	+		D46065J	4			YD157-YD170
0289	18		CQ		9-5	22-11-11	C01630	=L	D		D46065J	4			YL951-YR328
0290	20		CQ		10-3	22-11-12	C01631	=L	D		D46065J	25			YD157-YR328
0291	22		CQ		10-6	27-81-11	C00211	=L	D		D40368J	8			YC051-YL999, YR301-YR328
0291	22		PA		10-6	27-81-11	C00211	=L	D		D40368J	8			YN231-YN501
0292	20		CQ		8-3	28-21-11	C00359	=L	D		D40800J	14			YC051-YR323, YR325-YR328
0293	20		CQ		7-0	28-21-11	C00540	=L	D		D40558J	6			YC051-YC058
0293	20		CQ		6-11	28-21-11	C00540	=L	D		D40558J	6			YC059-YR328
0294	20		CQ		8-1	28-21-11	C00360	=L	D		D40812J	9			ALL
0295	20		CQ		7-1	28-22-11	C00361	=L	D		D40558J	7			YC051-YC058
0295	20		CQ		7-0	28-22-11	C00361	=L	D		D40558J	7			YC059-YR328
0296	22		PA		7-3	28-42-11	C00355	=L	D		D40536J	16			YC051-YC058
0296	22		PA		7-2	28-42-11	C00355	=L	D		D40536J	16			YC059-YR328
0297	18		CQ		6-11	28-44-11	C00032	=L	D		D00944	A1			ALL
0298	18		CQ		4-6	28-44-11	D00944	A2			D40386J	10			ALL
0299	20		CQ		4-6	28-44-11	D00944	D2			D40386J	25			ALL
0300	24		PK		1-7	33-25-11	SM00001		9		D01620	B2			ALL
0301	20		PA		10-1	33-25-11	D40218J		14		D01620	D2			YC051-YC057, YC059-YR328
0301	20		PA		11-1	33-25-11	D40218J		14		D01620	D2			YC058
0302	20		PA		10-1	33-25-11	D40218J		15		D01620	C2			YC051-YC057, YC059-YR328
0302	20		PA		11-1	33-25-11	D40218J		15		D01620	C2			YC058
0303	24		PK		1-7	33-25-11	SM00001		9		D01620	X1			ALL
0304	24		PK		9-0	33-25-11	D40218J		21		SM00001		9		YC051-YC057, YC059-YR328
0304	24		PK		10-1	33-25-11	D40218J		21		SM00001		9		YC058
0305	24		PK		0-7	33-25-11	SM00001		9		SM00002		9		ALL
0306	24		PK		1-9	33-25-11	SM00002		9		D01622	X1			ALL
0307	24		PK		1-9	33-25-11	SM00001		9		D01622	B2			ALL
0308	18		PA		10-2	33-25-11	D40218J		28		D01622	A2			YC051-YC057, YC059-YR328
0308	18		PA		11-3	33-25-11	D40218J		28		D01622	A2			YC058

WIRE LIST

D280A108

91-21-11

Section W0040

Page 47

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0044	286A0044				P6 (LOAD WIRES) (continued)										
0309	18		PA		1-9	33-25-11	SM00003		9		D01622	C2			ALL
0310	18		PA		1-9	33-25-11	SM00003		9		D01622	D2			ALL
0311	18		PA		9-0	33-25-11	D40218J	31			SM00003		9		YC051-YC057, YC059-YR328
0311	18		PA		10-1	33-25-11	D40218J	31			SM00003		9		YC058
0312	24		PK		7-9	33-25-11	D01620	X2			D40536J	18			ALL
0313	24		PK		6-8	33-25-11	SM00002		9		D40536J	30			ALL
0314	24		PK		7-10	33-25-11	D01622	X2			D40536J	9			ALL
0315	24		PK		4-7	33-25-11	D01622	B1			D46069J	6			ALL
0316	18		PA		5-0	33-25-11	D01622	D1			D40800J	21			YC051-YL952, YN231-YN501
0316	20		PA		5-0	33-25-11	D01622	D1			D40800J	39			YL953-YL999, YR301-YR328
0317	18		PA		10-2	33-25-11	D40218J	30			D01622	C1			YC051-YC057, YC059-YR328
0317	18		PA		11-3	33-25-11	D40218J	30			D01622	C1			YC058
0318	20		PA		10-1	33-25-11	D40218J	16			D01620	C1			YC051-YC057, YC059-YR328
0318	20		PA		11-1	33-25-11	D40218J	16			D01620	C1			YC058
0319	20		PA		10-1	33-25-11	D40218J	17			D01620	D1			YC051-YC057, YC059-YR328
0319	20		PA		11-1	33-25-11	D40218J	17			D01620	D1			YC058
0320	18		PA		10-2	33-25-11	D40218J	27			D01622	A1			YC051-YC057, YC059-YR328
0320	18		PA		11-3	33-25-11	D40218J	27			D01622	A1			YC058
0321	18		PA		11-8	33-25-11	D40218J	29			D40800J	23			YC051-YC057, YC059-YR328
0321	18		PA		12-8	33-25-11	D40218J	29			D40800J	23			YC058
0323	24		PK		9-9	33-29-11	D01640	C2			D40226J	5			YC051-YC057, YC059-YR328
0323	24		PK		10-9	33-29-11	D01640	C2			D40226J	5			YC058
0324	24		B6		1-5	33-29-11	D01640	C1			SM00004		9		ALL
0325	24		B6		1-5	33-29-11	D01640	B1			SM00004		9		ALL
0326	24		PK		9-9	33-29-11	D01640	B2			D40226J	6			YC051-YC057, YC059-YR328
0326	24		PK		10-9	33-29-11	D01640	B2			D40226J	6			YC058
0327	24		B6		4-11	33-29-11	SM00004		9		C00155	=L	D		ALL
0328	20		PA		4-6	33-32-11	D40396J	12			SM00005		9		ALL
0329	20		PA		4-6	33-32-11	SM00005		9		D40654J		9		ALL

WIRE LIST

D280A108

91-21-11

Section W0040

Page 48

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0044		286A0044				P6 (LOAD WIRES) (continued)									
	0330	20	PA		4-4	33-32-11	SM00005		9		D40536J	26			ALL
	0331	20	PA		8-9	33-32-11	D40536J	5			D40654J	10			ALL
	0332	20	PA		3-5	33-32-11	D40536J	6			D40444J	20			ALL
	0333	24	PK		4-5	33-25-11	D01620	B1			D46069J	5			ALL
	0334	20	CQ		8-10	30-41-11	C01650	=L	D		D40512J	6			YD160-YL967, YN231-YN235, YR324
	0334	20	CQ		10-8	30-41-11	C01650	=L	D		D40512J	6			YL968-YL999, YN236-YR323, YR325-YR328
	0335	20	PA		10-0	30-41-12	C01649	=L	D		D40536J	25			YD160-YR328
	0343	16	PA		9-4	33-45-11	D40502J	4			D40820J	10			YC051-YD170
	0344	20	PA		6-11	33-32-11	D40444J	19			SM00005		9		ALL
	0345	22	PA		7-10	52-51-11	C00137	=L	D		D40816J	9			YC051-YD154
	0346	22	PA		11-1	52-51-11	D40816J	11			D40226J	11			YC051-YC057, YC059-YD154
	0346	22	PA		12-1	52-51-11	D40816J	11			D40226J	11			YC058
	0348	20	GA		8-10	23-31-01	C00082	=L	D		D46069J	4			YC051-YC059
	0348	18	PA		8-10	23-31-01	C00082	=L	D		D46069J	4			YC060-YR328
	0349	22	PA		8-9	23-31-06	C00080	=L	D		D46061J	10			YC051-YN260
	0350	20	CQ		9-10	22-11-11	C01046	=L	D		D46065J	13			YC051-YC057
	0350	20	CQ		9-9	22-11-11	C01046	=L	D		D46065J	13			YC058-YR328
	0351	20	CQ		9-9	22-11-11	C01042	=L	D		D46061J	7			YC051-YC057
	0351	20	CQ		9-8	22-11-11	C01042	=L	D		D46061J	7			YC058-YR328
	0352	20	CQ		9-9	22-11-12	C00716	=L	D		D46065J	12			ALL
	0353	20	CQ		9-10	22-11-12	C01047	=L	D		D46065J	14			ALL
	0366	20	CQ		1-1	33-18-11	SM00018		9		SM00021		9		ALL
	0367	24	PK		1-3	24-32-11	D11714B	17			GD00630	AC..	1A		ALL
	0368	24	PK		1-3	24-32-11	D11714B	6			GD00630	AC..	1A		ALL
	0393	16	PA		8-8	31-62-21	C01364	=L	D		D46065J	1			ALL
	0394	16	PA		8-8	31-62-21	C01366	=L	D		D46065J	2			ALL
	0395	16	PA		8-9	31-62-21	C01373	=L	D		D46065J	10			ALL
	0396	22	PA		8-10	31-62-21	C01370	=L	D		D46065J	29			ALL
	0397	16	PA		8-6	31-62-21	C01360	=L	D		D46063J	19			ALL
	0398	16	CQ		8-6	31-62-21	C01362	=L	D		D46063J	15			YC051-YL999, YR301-YR328
	0398	16	CQ		7-8	31-62-21	C01362	=L	D		D46063J	15			YN231-YN501
	0408	22	CQ		8-4	28-41-11	C00398	=L	D		D40812J	17			ALL
	0409	22	PA		6-11	28-41-11	C00397	=L	D		D00944	B3			ALL
	0410	22	CQ		6-10	28-41-11	C01441	=L	D	*	D00944	B1			ALL

WIRE LIST

D280A108

91-21-11

Section W0040

Page 49

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity			
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice	
W0044	286A0044				P6 (LOAD WIRES) (continued)											
0411	22		CQ		6-10	28-41-11	C01441	=L	D	*	D00944	D1		ALL		
0412	22		CQ		4-9	28-41-11	D00944	B2			D40800J	15		ALL		
0413	22		PA		10-6	27-83-21	C01070	=L	D		D40386J	3		YC051-YC057		
0413	22		PA		10-5	27-83-21	C01070	=L	D		D40386J	3		YC058-YR328		
0414	20		CQ		9-9	73-22-11	C01315	=L	D		D40820J	17		YC051-YC057		
0414	20		CQ		9-8	73-22-11	C01315	=L	D		D40820J	17		YC058-YR328		
0415	20		PA		10-2	73-22-11	C01391	=L	D		D40750J	3		YC051-YC057		
0415	20		PA		10-1	73-22-11	C01391	=L	D		D40750J	3		YC058-YR328		
0416	24		PK		9-10	73-22-31	C01313	=L	D		D40820J	1		YC051-YC057		
0416	24		PK		9-9	73-22-31	C01313	=L	D		D40820J	1		YC058-YL999, YR301-YR328		
0416	24		B6		9-9	73-22-31	C01313	=L	D		D40820J	1		YN231-YN501		
0417	20		CQ		9-8	74-11-11	C00459	=L	D		D40812J	11		YC051-YC057		
0417	20		CQ		9-7	74-11-11	C00459	=L	D		D40812J	11		YC058-YR328		
0418	20		CQ		9-7	74-11-11	C00151	=L	D		D40820J	3		ALL		
0419	20		CQ		8-0	76-21-11	C01320	=L	D		D40800J	8		ALL		
0420	24		B6		6-10	76-21-11	C01395	=L	D		D40550J	22		YC051-YC058		
0420	24		B6		6-8	76-21-11	C01395	=L	D		D40550J	22		YC059-YR328		
0421	20		CQ		7-10	76-21-21	C01321	=L	D		D40812J	12		ALL		
0422	24		B6		6-10	76-21-21	C01396	=L	D		D40558J	15		YC051-YC058		
0422	24		B6		6-9	76-21-21	C01396	=L	D		D40558J	15		YC059-YR328		
0423	24		PK		10-5	77-31-11	C01076	=L	D		D40386J	17		YC051-YC057		
0423	24		PK		10-4	77-31-11	C01076	=L	D		D40386J	17		YC058-YR328		
0424	18		CQ		9-11	78-32-61	C01267	=L	D		D40812J	6	18	YC051-YC057		
0424	18		CQ		9-10	78-32-61	C01267	=L	D		D40812J	6	18	YC058-YR328		
0425	20		CQ		10-1	78-34-21	C00277	=L	D		D40812J	10		YC051-YC057		
0425	20		CQ		10-0	78-34-21	C00277	=L	D		D40812J	10		YC058-YR328		
0426	20		CQ		10-0	78-35-21	C01413	=L	D		D40812J	16		YC051-YC057		
0426	20		CQ		9-11	78-35-21	C01413	=L	D		D40812J	16		YC058-YR328		
0427	20		PA		10-0	78-36-21	C01004	=L	D		D40386J	15		ALL		
0428	20		CQ		4-11	80-11-11	C00154	=L	D		D40558J	4		YC051-YC058		
0428	20		CQ		4-7	80-11-11	C00154	=L	D		D40558J	4		YC059-YR328		
0429	14		PA		6-9	21-25-11	C00884	A1	D		R00331	A1	D	ALL		
0430	14		PA		6-8	21-25-11	C00884	B1	D		R00331	B1	D	ALL		
0431	14		CQ		6-9	21-25-11	C00884	C1	D		R00331	C1	D	YC051-YC059		
0431	14		PA		6-9	21-25-11	C00884	C1	D		R00331	C1	D	YC060-YR328		
0432	22		PA		6-11	21-25-11	C01015	=L	D		R00331	X1	C	YN231-YN501		
0433	22		PA		6-1	21-25-11	R00331	X2	C		D40800J	16		YN231-YN501		
0436	14		PA		5-2	21-25-11	R00331	A2	D		D40386J	1		ALL		

WIRE LIST

D280A108

91-21-11

Section W0040

Page 50

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0044		286A0044			P6 (LOAD WIRES) (continued)											
0437		14		PA		5-3	21-25-11	R00331	B2	D		D40386J	2			ALL
0438		14		PA		5-2	21-25-11	R00331	C2	D		D40386J	4			ALL
0440		20		CQ		2-6	21-31-11	C01269	=L	D		SM00034		9		ALL
0441		20		CQ		5-0	21-31-11	D40550J	1			SM00034		9		YC051-YC058
0441		20		CQ		4-11	21-31-11	D40550J	1			SM00034		9		YC059-YR328
0442		20		CQ		4-11	21-31-11	D10820	7			SM00034		9		ALL
0443		24		B6		8-9	21-31-11	D10820	3			D40550J	44			ALL
0444		20		CQ		3-0	21-31-11	D10820	2			GD00626	DC..	1A		YC051-YR323, YR325-YR328
0445		20		CQ		7-5	21-31-22	C01270	=L	D		D40512J	11			YC051-YC058
0445		20		CQ		7-4	21-31-22	C01270	=L	D		D40512J	11			YC059-YR328
0446		24		B6		1-1	21-31-22	D10820	4			D10822	2			ALL
0447		24		B6		1-1	21-31-22	D10822	4			D10824	2			ALL
0448		24		B6		8-8	21-31-22	D10822	7			D40512J	8			ALL
0449		24		B6		8-8	21-31-22	D10824	4			D40512J	1			ALL
0450		20		CQ		3-0	21-31-22	D10822	3			GD00626	DC..	1A		YC051-YR323, YR325-YR328
0451		20		PA		6-11	21-31-23	C01271	=L	D		D40386J	22			YC051-YD157
0452		24		B6		7-6	21-31-23	C01272	=L	D		D40558J	5			YC051-YC058
0452		24		B6		7-5	21-31-23	C01272	=L	D		D40558J	5			YC059-YR328
0453		24		PK		5-4	21-31-23	D10824	7			D40386J	13			YC051-YD157
0454		22		PA		1-3	21-31-23	D10824	3			GD00622	DC..	E		ALL
0455		24		PK		4-0	21-31-25	C01273	=L	D		T00371	HV	D		YC051-YC057
0455		24		PK		3-11	21-31-25	C01273	=L	D		T00371	HV	D		YC058-YR328
0456		20		PA		1-9	21-31-25	T00371	GND	D		GD00608	AC..	E		ALL
0457		24		PK		4-1	21-31-25	D10762	A3			T00371	LV1	D		ALL
0458		24		PK		8-5	21-31-25	D10762	A2			D40536J	17			ALL
0459		22		CQ		7-11	21-33-11	C00129	=L	D		D40550J	6			YC051-YC058
0459		22		CQ		7-10	21-33-11	C00129	=L	D		D40550J	6			YC059-YR328
0461		24		B6		8-1	21-51-11	C00262	=L	D		D40550J	26			YC051-YC058
0461		24		B6		7-11	21-51-11	C00262	=L	D		D40550J	26			YC059-YR328
0462		22		CQ		10-3	21-51-14	C00265	=L	D		D40444J	22			YN231-YN501
0463		24		B6		10-2	21-51-14	D40444J	2			C00399	=L	D		YC051-YC057
0463		24		B6		10-1	21-51-14	D40444J	2			C00399	=L	D		YC058-YL999, YR301-YR323, YR325-YR328
0463		24		B6		10-1	21-51-14	C00399	=L	D		D40444J	2			YN231-YN501
0464		24		B6		9-10	21-51-15	C00257	=L	D		D40444J	21			YN231-YN501
0465		24		B6		10-4	21-51-16	C00344	=L	D		D40444J	3			YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W0040

Page 51

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W0044	286A0044				P6 (LOAD WIRES) (continued)											
0466	24	B6		7-10	21-51-21	C00263		=L	D		D40558J	8			YC051-YC058	
0466	24	B6		7-9	21-51-21	C00263		=L	D		D40558J	8			YC059-YR328	
0467	22	PA		7-10	21-51-24	C00266		=L	D		D40386J	7			YN231-YN501	
0468	24	PK		7-8	21-51-24	C00400		=L	D		D40386J	19			YC051-YR323, YR325-YR328	
0469	24	PK		7-10	21-51-26	C00345		=L	D		D40386J	21			YN231-YN501	
0470	24	B6		8-3	21-61-21	C00268		=L	D		D40532J	13			YN231-YN501	
0471	24	B6		8-2	21-61-21	C00267		=L	D		D40532J	14			YN231-YN501	
0472	24	B6		7-8	21-61-21	C00124		=L	D		D40532J	20			YN231-YN501	
0473	24	PK		7-10	21-61-22	C00258		=L	D		D40536J	24			YN231-YN501	
0474	20	PA		7-9	21-61-51	C00076		=L	D		D40536J	21			YC051-YC058	
0474	20	PA		7-8	21-61-51	C00076		=L	D		D40536J	21			YC059-YR328	
0481	24	PK		7-11	36-11-11	C00797		=L	D		D40812J	18			ALL	
0482	24	B6		8-4	36-11-11	C00796		=L	D		D40800J	5			ALL	
0483	24	B6		8-2	36-11-11	C00259		=L	D		D40532J	4			YC051-YC058	
0483	24	B6		8-1	36-11-11	C00259		=L	D		D40532J	4			YC059-YR328	
0484	24	PK		7-10	36-21-11	C00077		=L	D		D40536J	8			YC051-YC058	
0484	24	PK		7-8	36-21-11	C00077		=L	D		D40536J	8			YC059-YR328	
0485	22	PA		7-0	30-31-11	C00569		=L	D		D40536J	20			YC051-YC058	
0485	22	PA		6-11	30-31-11	C00569		=L	D		D40536J	20			YC059-YR328	
0486	22	CQ		7-0	30-31-12	C00570		=L	D		D40512J	9			YC051-YC058	
0486	22	CQ		6-11	30-31-12	C00570		=L	D		D40512J	9			YC059-YR328	
0491	12	CQ		8-5	30-41-11	C00228		=L	D		D41430J	1			YC051-YL954, YN231-YN235	
0491	12	CQ		8-5	30-41-11	C00228		=L	M		D41430J	1			YL955-YL999, YN236-YR328	
0492	16	CQ		8-4	30-41-11	C00393		=L	D		D41430J	2			YC051-YL954, YN231-YN235	
0492	16	CQ		8-4	30-41-11	C00393		=L	M		D41430J	2			YL955-YL999, YN236-YR328	
0493	20	CQ		8-11	30-41-11	C00229		=L	D		D40512J	6			YC051-YC058	
0493	20	CQ		8-10	30-41-11	C00229		=L	D		D40512J	6			YC059-YD158	
0494	12	PA		7-1	30-41-12	C00394		=L	D		D40386J	8			YC051-YL954, YN231-YN235	
0494	12	CQ		7-1	30-41-12	C00394		=L	M		D40386J	8			YL955-YL999, YN236-YR328	
0495	16	PA		7-2	30-41-12	C00392		=L	D		D40386J	6			YC051-YC057	
0495	16	PA		7-1	30-41-12	C00392		=L	D		D40386J	6			YC058-YL954, YN231-YN235	

WIRE LIST
D280A108

91-21-11
Section W0040
Page 52
Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0044	286A0044				P6 (LOAD WIRES) (continued)										
0495	16		CQ		7-1	30-41-12	C00392	=L	M		D40386J	6			YL955-YL999, YN236-YR328
0496	20		PA		10-0	30-41-12	C00395	=L	D		D40536J	25			YC051-YD158
0497	20		PA		1-5	30-41-12	D40536J	12			D40582J	7			ALL
0498	20		CQ		8-3	49-41-11	C01424	=L	D		D40352J	24			ALL
0500	20		CQ		8-7	49-62-11	C00033	=L	D	*	D40352J	3			ALL
0501	20		CQ		10-11	49-62-11	C01344	=L	D		D40812J	7			YC051-YC057
0501	20		CQ		10-10	49-62-11	C01344	=L	D		D40812J	7			YC058-YR328
0502	22		CQ		10-11	23-51-51	C00085	=L	D		D40386J	11			YC051-YC057
0502	22		CQ		10-10	23-51-51	C00085	=L	D		D40386J	11			YC058-YR328
0503	22		CQ		10-10	23-51-51	C00083	=L	D		D40386J	12			YC051-YC057
0503	22		CQ		10-9	23-51-51	C00083	=L	D		D40386J	12			YC058-YR328
0504	22		CQ		8-5	23-51-51	C00086	=L	D		D40444J	23			YC051-YC057
0504	22		CQ		8-2	23-51-51	C00086	=L	D		D40444J	23			YC058-YR328
0505	22		CQ		8-4	23-51-51	C00084	=L	D		D40444J	24			YC051-YC057
0505	22		CQ		8-1	23-51-51	C00084	=L	D		D40444J	24			YC058-YR328
0506	20		CQ		9-10	22-14-11	C00374	=L	D		D46061J	28			YC051-YC057
0506	20		CQ		9-9	22-14-11	C00374	=L	D		D46061J	28			YC058-YR328
0507	20		CQ		9-11	22-18-11	C01064	=L	D		D46065J	3			YC051-YC057
0507	20		CQ		9-10	22-18-11	C01064	=L	D		D46065J	3			YC058-YR328
0508	20		CQ		9-10	22-18-11	C01037	=L	D		D46061J	4			YC051-YC057
0508	20		CQ		9-9	22-18-11	C01037	=L	D		D46061J	4			YC058-YR328
0509	22		PA		9-5	27-32-21	C01207	=L	D		D46067J	4			ALL
0510	22		PA		9-1	27-32-21	C01206	=L	D		D46063J	5			ALL
0511	22		PA		9-0	27-32-21	C01393	=L	D		D46063J	6			ALL
0512	24		B6		8-7	24-33-11	C00136	=L	D		D40550J	42			YC051-YC058
0512	24		B6		8-6	24-33-11	C00136	=L	D		D40550J	42			YC059-YR328
0513	24		PK		9-2	32-41-11	C00195	=L	D		D40750J	2			ALL
0514	24		B6		8-4	32-41-11	C00196	=L	D		D46069J	8			ALL
0515	20		CQ		8-0	31-52-71	TB5060B	4	E		D40822J	18			ALL
0516	20		CQ		7-7	31-52-71	C01278	=L	D		TB5060B	5	E		YC051-YC057
0516	20		CQ		7-6	31-52-71	C01278	=L	D		TB5060B	5	E		YC058-YD153
0516	20		CQ		7-10	31-52-71	C01278	=L	D		TB5060B	5	E		YD154-YR328
0517	20		CQ		7-11	31-52-71	TB5060B	6	E		D40822J	19			ALL
0519	20		CQ		13-4	34-61-18	TB5060B	9	E		D40512J	5			YC051-YC057
0519	20		CQ		13-3	34-61-18	TB5060B	9	E		D40512J	5			YC058
0519	20		CQ		13-3	31-32-15	TB5060B	9	E		D40512J	5			YC059
0519	20		CQ		3-2	31-32-15	TB5060B	9	E		D40512J	5			YC060-YR328
0520	20		PA		9-7	34-21-21	C00426	=L	D		D46065J	7			YC051-YC057

WIRE LIST

D280A108

91-21-11

Section W0040

Page 53

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0044	286A0044				P6 (LOAD WIRES) (continued)										
0520	20		PA		9-3	34-21-21	C00426	=L	D		D46065J	7			YC058-YR328
0521	20		PA		9-6	34-21-21	C01008	=L	D		D46065J	28			YC051-YC057
0521	20		PA		9-3	34-21-21	C01008	=L	D		D46065J	28			YC058-YR328
0522	16		CQ		9-7	34-21-21	C01010	=L	D		D46061J	23			YC051-YC057
0522	16		CQ		9-3	34-21-21	C01010	=L	D		D46061J	23			YC058-YR328
0523	22		PA		9-2	34-51-41	C01377	=L	D		D46065J	5			ALL
0524	24		B6		1-6	24-31-12	D11714B	60			GD00632	DC..	1A		ALL
0525	24		B6		1-3	24-31-12	D11714B	67			GD00630	DC..	1A		ALL
0526	24		B6		1-7	24-31-12	D11714A	24			GD00632	DC..	1A		ALL
0527	08		CQ		3-9	24-31-12	D11714A	A7			TB5060I	1	E		ALL
0528	24		B6		6-8	24-31-12	D11714A	5			D40558J	3			ALL
0529	24		B6		6-8	24-31-12	D11714A	18			D40558J	13			ALL
0530	24		B6		6-8	24-31-12	D11714A	20			D40558J	12			ALL
0531	24		B6		6-8	24-31-12	D11714A	21			D40558J	11			ALL
0532	24		B6		6-8	24-31-12	D11714A	7			D40558J	2			ALL
0538	22		CQ		10-10	29-32-11	C00306	=L	D		D46052J	25			YC051-YC057
0538	22		CQ		10-9	29-32-11	C00306	=L	D		D46052J	25			YC058-YR328
0539	20		CQ		3-2	33-18-62	D10046	12			GD00624	DC..	1		YC051-YC057
0539	20		CQ		3-4	33-18-62	D10046	12			GD00624	DC..	1		YC058-YR328
0540	20		CQ		5-0	33-18-32	D40550J	9			SM00040	9			YC051-YC058
0540	20		CQ		4-11	33-18-32	D40550J	9			SM00040	9			YC059-YR328
0541	24		B6		7-10	21-43-21	C01444	=L	D		D40800J	24			ALL
0542	24		B6		1-0	21-43-21	C01444	=L	D		C01445	=B	D		ALL
0543	24		B6		8-1	21-43-21	C01445	=L	D		D40750J	19			ALL
0544	20		CQ		8-8	33-14-11	C01425	=L	D		D46065J	30			ALL
0545	20		PA		10-0	27-25-11	C01447	CAP	Y		D46063J	12			YC051-YC057
0545	20		PA		9-11	27-25-11	C01447	CAP	Y		D46063J	12			YC058-YD155
0547	20		CQ		8-3	33-18-62	C01179	=L	D	*	D40822J	4			ALL
0548	20		CQ		8-4	33-18-62	C01180	=L	D	*	D40822J	14			ALL
0549	24		B6		6-4	24-31-11	D11712B	9			D40550J	40			ALL
0550	24		B6		3-6	24-31-11	D11712B	25			GD00632	DC..	1A		ALL
0551	24		B6		1-6	24-31-11	GD00632	DC..	1A		D11714B	55			YC051-YC059
0551	24		B6		1-6	24-31-11	D11714B	55			GD00632	DC..	1A		YC060-YR328
0552	24		B6		6-4	24-31-12	D11712B	4			D40550J	45			ALL
0553	24		B6		6-9	24-31-12	D11714B	30			D40550J	51			ALL
0554	20		CQ		11-5	22-23-11	D40218J	25			D46067J	8			YC051-YC057, YC059-YR328
0554	20		CQ		12-6	22-23-11	D40218J	25			D46067J	8			YC058
0561	22		PA		9-2	34-31-21	C01480	=L	D		D46061J	1			ALL

WIRE LIST

D280A108

91-21-11

Section W0040

Page 54

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0044		286A0044			P6 (LOAD WIRES) (continued)											
0562		24		PK		10-4	27-52-11	C01443	=L	D		D46061J	15			YC051-YC057
0562		24		PK		10-3	27-52-11	C01443	=L	D		D46061J	15			YC058-YR328
0563		24		PK		4-2	33-29-11	D01640	X1			D40654J	12			ALL
0564		20		PA		2-7	33-29-11	D01640	X2			GD00620	DC..	1A		ALL
0565		20		GA		9-7	23-34-01	C01456	=L	D		D40750J	14			YC051-YC059
0565		20		PA		9-7	23-34-01	C01456	=L	D		D40750J	14			YC060-YN260
0565		20		PA		9-7	44-21-26	C01456	=L	D		D40750J	14			YN501-YR328
0566		22		PA		8-1	25-51-21	C01139	=L	D		D40368J	14			YC051-YC057
0566		22		PA		8-2	25-51-21	C01139	=L	D		D40368J	14			YC058-YL999, YR301-YR328
0571		22		CQ		7-8	23-27-11	C00744	=L	D		D40218J	7			YC051-YD157
0572		22		CQ		8-10	23-27-11	C00743	=L	D		D46067J	13			YC051-YD157
0573		22		CQ		7-9	23-27-13	C01255	=L	D		D40218J	6			YC051-YD157
0574		16		CQ		11-5	23-12-31	D40218J	34			D46067J	15			YC051-YC057, YC059-YR328
0574		16		CQ		12-6	23-12-31	D40218J	34			D46067J	15			YC058
0575		16		CQ		11-5	23-12-31	D40218J	35			D46067J	19			YC051-YC057, YC059-YD157
0575		16		CQ		12-6	23-12-31	D40218J	35			D46067J	19			YC058
0580		24		B6		9-11	76-21-21	C01318	=L	D		D40820J	14			YC051-YC057
0580		24		B6		9-10	76-21-21	C01318	=L	D		D40820J	14			YC058-YR328
0581		24		B6		10-6	76-21-21	C01319	=L	D		D40750J	13			YC051-YC057
0581		24		B6		10-5	76-21-21	C01319	=L	D		D40750J	13			YC058-YR328
0582		22		PA		2-5	24-28-11	D40352J	14			SM00043	9			YC051-YC057
0582		22		PA		2-7	24-28-11	D40352J	14			SM00043	9			YC058-YR328
0583		22		PA		7-11	24-28-11	C01467	=L	D		D40352J	16			ALL
0584		24		PK		7-10	24-33-13	C00023	=L	D		D40352J	18			ALL
0585		24		B6		7-9	24-33-13	C00026	=L	D		D40352J	29			ALL
0586		24		B6		8-1	24-33-13	C00134	=L	D		D40352J	15			ALL
0587		24		B6		8-2	24-33-13	C01466	=L	D		D40352J	19			ALL
0588		24		B6		8-3	24-33-13	C00136	=L	D		D40352J	30			ALL
0589		24		PK		8-0	24-33-13	C01338	=L	D		D40352J	26			ALL
0590		22		PA		7-1	24-28-11	D40536J	3			SM00043	9			YC051-YC057
0590		22		PA		7-0	24-28-11	D40536J	3			SM00043	9			YC058-YR328
0591		22		PA		10-5	27-81-11	C01468	=L	D		D46065J	21			YC051-YC057
0591		22		PA		10-4	27-81-11	C01468	=L	D		D46065J	21			YC058-YR328
0592		20		CQ		10-3	27-81-51	D40352J	32			C00210	=L	D	*	YC051-YL999, YR301-YR328
0592		20		CQ		10-3	27-81-51	C00210	=L	D	*	D40352J	32			YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W0040

Page 55

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To				Effectivity
Wire No.	GA	CO TY	FT-IN		Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W0044	286A0044			P6 (LOAD WIRES) (continued)											
0593	24	PK		7-9	36-21-11	C01469	=L	D		D40386J	5			ALL	
0594	24	PK		8-3	36-21-11	C01470	=L	D		D40800J	4			ALL	
0595	24	B6		10-5	21-51-12	C01157	=L	D		D40444J	13			YC051-YC057	
0595	24	B6		10-4	21-51-12	C01157	=L	D		D40444J	13			YC058-YL999, YR301-YR328	
0596	24	B6		10-5	21-51-12	C01158	=L	D		D40444J	17			YC051-YC057	
0596	24	B6		10-4	21-51-12	C01158	=L	D		D40444J	17			YC058-YL999, YR301-YR328	
0597	24	B6		10-7	21-51-12	C01159	=L	D		D40444J	18			YC051-YC057	
0597	24	B6		10-6	21-51-12	C01159	=L	D		D40444J	18			YC058-YL999, YR301-YR328	
0598	24	B6		10-5	21-51-14	C00555	=L	D		D40444J	22			YC051-YC057	
0598	24	B6		10-3	21-51-14	C00555	=L	D		D40444J	22			YC058-YL999, YR301-YR328	
0599	24	B6		10-1	21-51-15	C01176	=L	D		D40444J	21			YC051-YC057	
0599	24	B6		10-0	21-51-15	C01176	=L	D		D40444J	21			YC058-YL999, YR301-YR328	
0601	24	PK		8-0	21-61-14	C01169	=L	D		D41832J	14			YC051-YL999, YR301-YR323, YR325-YR328	
0602	24	PK		8-2	21-61-14	C01170	=L	D		D41832J	8			YC051-YL999, YR301-YR323, YR325-YR328	
0603	24	B6		8-0	21-51-25	C01177	=L	D		D41832J	4			YC051-YL999, YR301-YR323, YR325-YR328	
0604	24	B6		8-0	21-61-13	C01166	=L	D		D41832J	15			YC051-YL999, YR301-YR323, YR325-YR328	
0605	24	PK		8-0	21-61-13	C01167	=L	D		D41832J	6			YC051-YL999, YR301-YR323, YR325-YR328	
0606	24	B6		10-0	21-61-11	C01164	=L	D		D40444J	3			YC051-YC057	
0606	24	B6		9-10	21-61-11	C01164	=L	D		D40444J	3			YC058-YL999, YR301-YR328	
0607	24	PK		8-0	21-61-11	C01163	=L	D		D40532J	20			YC051-YC058	
0607	24	PK		7-11	21-61-11	C01163	=L	D		D40532J	20			YC059-YL999, YR301-YR323, YR325-YR328	

WIRE LIST

D280A108

91-21-11

Section W0040

Page 56

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W0044	286A0044	P6 (LOAD WIRES) (continued)													
0608	24	PK	8-1	21-51-22	C01160	=L	D		D41832J	1				YC051-YL999, YR301-YR323, YR325-YR328	
0609	24	PK	8-2	21-51-22	C01161	=L	D		D41832J	2				YC051-YL999, YR301-YR323, YR325-YR328	
0610	24	PK	8-3	21-51-22	C01162	=L	D		D41832J	3				YC051-YL999, YR301-YR323, YR325-YR328	
0611	24	PK	7-10	21-51-24	C01178	=L	D		D40386J	7				YC051-YL999, YR301-YR328	
0612	20	PA	7-10	21-61-15	C01172	=L	D		D40536J	24				YC051-YC058	
0612	20	PA	7-9	21-61-15	C01172	=L	D		D40536J	24				YC059-YL999, YR301-YR328	
0613	24	PK	6-11	21-25-11	C01023	=L	D		R00331	X1	C			YC051-YD157, YL951-YL999, YR301-YR328	
0613	24	PK	6-11	21-25-11	C01023	=L	D		R00331	X1	C			YD158-YD170	
0614	24	PK	6-1	21-25-11	R00331	X2	C		D40800J	16			*	YC051-YD157, YL951-YL999, YR301-YR328	
0614	24	PK	6-1	21-25-11	R00331	X2	C	*	D40800J	16				YD158-YD170	
0615	22	PA	8-11	31-33-01	C01216	=L	D		D40352J	12				ALL	
0616	20	CQ	9-1	34-61-11	C01239	=L	D		D46067J	1				YC051-YC059	
0616	20	PA	9-1	34-61-11	C01239	=L	D		D46067J	1				YC060-YR328	
0620	24	PK	2-7	32-44-11	D40822J	12			D40654J	3				YC051-YC059	
0620	24	PK	3-2	32-44-11	D40822J	12			D40654J	3				YC060-YD157	
0624	22	CQ	2-11	34-24-15	D40218J	11			D40444J	1				YD158	
0624	20	CQ	2-11	34-24-15	D40218J	11			D40444J	1				YD160-YL999	
0624	20	CQ	2-4	34-24-15	D40218J	11			D40444J	1				YN231-YR328	
0636	20	PA	9-1	23-31-01	C01583	=L	D		D46069J	3				YC060-YR328	
0637	24	B6	8-5	21-27-21	C01435	=L	D		D40812J	19				ALL	
0638	24	PK	8-2	21-27-21	C01436	=L	D		D40396J	11				ALL	
0641	24	B6	8-7	21-27-31	C01117	=L	D		D40800J	22				ALL	
0642	24	B6	8-8	21-27-31	C01116	=L	D		D40822J	17				ALL	
0643	20	PA	10-0	27-31-11	C01464	=L	D		D40386J	30				ALL	
0645	20	PA	8-3	28-21-21	C01471	=L	D		D12006	5				ALL	
0646	20	PA	7-9	28-21-21	GD00638	ST..	1A		D12006	8				ALL	
0647	20	CQ	7-6	28-21-21	C01472	=L	D		R00669	=A	\$		*	YC051-YC052	

WIRE LIST

D280A108

91-21-11

Section W0040

Page 57

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W0044	286A0044	P6 (LOAD WIRES) (continued)			
0648	20 CQ	6-1 28-21-21	R00669 =A \$ *	D12006 11	YC051-YC052
0649	20 CQ	6-1 28-21-21	R00669 =C F *	D12006 12	ALL
0650	20 GA	5-4 23-32-11	D45233J 15	GD00642 AC.. 1A	YC059
0650	20 PA	5-4 23-32-11	D45233J 15	GD00642 AC.. 1A	YC060-YN260
0651	20 PA	7-9 28-21-21	GD00638 DC.. 1A	D12006 6	ALL
0654	20 PA	0-7 28-21-21	D12006 1	D12006 2	YC051-YL999, YR301-YR328
0654	20 PA	1-4 28-21-21	D12006 1	D12006 2	YN231-YN501
0655	20 PA	7-9 28-21-21	D12006 7	GD00638 DC.. 1A	ALL
0656	16 PA	9-4 33-45-11	D40502J 4	D40820J 11	YL951-YR328
0665	24 PK	11-2 26-14-11	D40352J 21	D40226J 10	YC051-YC057, YC059-YD170
0665	24 PK	12-2 26-14-11	D40352J 21	D40226J 10	YC058
0677	20 PA	7-7 23-32-11	C01451 =L D	D45233J 1	YC051-YC058
0677	20 GA	7-7 23-32-11	C01451 =L D	D45233J 14	YC059
0677	20 PA	7-7 23-32-11	C01451 =L D	D45233J 14	YC060-YN260
0678	20 GA	7-5 23-32-31	C01452 =L D	D45233J 3	YC051-YC059
0678	20 PA	7-5 23-32-31	C01452 =L D	D45233J 3	YC060-YN260
0679	20 PA	5-3 23-32-31	GD00642 AC.. 1A	D45233J 4	YC051-YC057
0679	20 PA	13-0 23-32-31	GD00642 AC.. 1A	D45233J 4	YC058
0679	20 PA	5-4 23-32-31	GD00642 AC.. 1A	D45233J 4	YC059
0679	20 PA	5-4 23-32-31	D45233J 4	GD00642 AC.. 1A	YC060-YN260
0680	20 GA	7-4 23-32-41	C01453 =L D	D45233J 5	YC051-YC058
0680	20 GA	7-5 23-32-41	C01453 =L D	D45233J 5	YC059
0680	20 PA	7-5 23-32-41	C01453 =L D	D45233J 5	YC060-YN260
0681	20 PA	5-3 23-32-41	GD00642 AC.. 1A	D45233J 6	YC051-YC057
0681	20 PA	13-0 23-32-41	GD00642 AC.. 1A	D45233J 6	YC058
0681	20 PA	5-4 23-32-41	GD00642 AC.. 1A	D45233J 6	YC059
0681	20 PA	5-4 23-32-41	D45233J 6	GD00642 AC.. 1A	YC060-YN260
0682	20 GA	7-4 23-32-51	C01454 =L D	D45233J 7	YC051-YC059
0682	20 PA	7-4 23-32-51	C01454 =L D	D45233J 7	YC060-YN260
0683	20 PA	5-3 23-32-51	GD00642 AC.. 1A	D45233J 8	YC051-YC057
0683	20 PA	13-0 23-32-51	GD00642 AC.. 1A	D45233J 8	YC058
0683	20 PA	5-4 23-32-51	GD00642 AC.. 1A	D45233J 8	YC059
0683	20 PA	5-4 23-32-51	D45233J 8	GD00642 AC.. 1A	YC060-YN260
0684	20 GA	7-2 23-32-61	C01455 =L D	D45233J 9	YC051-YC059
0684	20 PA	7-2 23-32-61	C01455 =L D	D45233J 9	YC060-YN260
0685	20 PA	5-3 23-32-61	GD00642 AC.. 1A	D45233J 10	YC051-YC057
0685	20 PA	13-0 23-32-61	GD00642 AC.. 1A	D45233J 10	YC058

WIRE LIST

D280A108

91-21-11

Section W0040

Page 58

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0044		286A0044			P6 (LOAD WIRES) (continued)											
0685		20		PA		5-4	23-32-61	GD00642	AC..	1A		D45233J	10			YC059
0685		20		PA		5-4	23-32-61	D45233J	10			GD00642	AC..	1A		YC060-YN260
0692		08		PA		1-4	24-31-12	GD00644	ST..	F		D11712B	A5			ALL
0693		22		PA		9-0	23-32-12	D40550J	20			D46069J	1			YC051-YD157
0693		22		PA		9-0	23-32-14	D40550J	20			D46069J	1			YD158-YN260
0693		22		PA		9-0	44-21-22	D40550J	20			D46069J	1			YN501-YR328
0698		22		CQ		7-8	23-27-31	C01483	=L	D		D40218J	2			YD158-YR328
0701		24		B6		7-1	23-24-11	C01495	=L	D		D40536J	4			YC051-YC058
0701		24		B6		7-0	23-24-11	C01495	=L	D		D40536J	4			YC059
0701		24		PK		7-0	23-24-11	C01495	=L	D		D40536J	4			YC060-YD170
0702		20		GA		9-6	23-34-01	C01101	=L	D		D40750J	15			YC051-YC059
0702		20		PA		9-6	23-34-01	C01101	=L	D		D40750J	15			YC060-YD157
0703		10		CQ		8-8	49-62-11	C00033	=L	D	*	TB5060B	10	E		YC051-YC057
0703		10		CQ		8-7	49-62-11	C00033	=L	D	*	TB5060B	10	E		YC058-YR328
0704		20		CQ		8-9	49-62-11	C00033	=L	D	*	D40558J	9			YC051-YC058
0704		20		CQ		8-8	49-62-11	C00033	=L	D	*	D40558J	9			YC059-YR328
0708		20		CQ		2-7	33-18-11	SM00053		9		D46052J	4			YC051-YC057
0708		20		CQ		2-8	33-18-11	SM00053		9		D46052J	4			YC058-YR328
0709		20		CQ		3-0	33-18-11	SM00053		9		D40750J	9			YC051-YC057
0709		20		CQ		3-1	33-18-11	SM00053		9		D40750J	9			YC058-YR328
0713		22		PA		9-0	31-35-03	C01196	=L	D		D40352J	17			YN236-YR328
0747		20		PA		7-6	52-71-13	C01514	=L	D		D40218J	22			YC051-YC057
0747		20		PA		7-3	52-71-13	C01514	=L	D		D40218J	22			YC058-YR328
0748		20		PA		10-3	52-71-14	C01515	=L	D		D40750J	16			YC051-YC057
0748		20		PA		10-2	52-71-14	C01515	=L	D		D40750J	16			YC058-YR328
0756		20		PA		9-2	34-41-11	C00120	=L	D		D40800J	37			YC053-YR328
0762		20		CQ		7-4	33-18-37	C00315	=L	D	*	D40550J	28			YC051-YC058
0762		20		CQ		7-3	33-18-37	C00315	=L	D	*	D40550J	28			YC059-YR328
0763		20		PA		2-2	23-15-11	D40218J	8			D40165J	1			YC051-YD157
0765		20		CQ		10-1	31-32-15	D40218J	4			TB0610X	A009	1A		YL951-YR328
0769		20		PA		9-0	23-11-21	C00857	A2	D		D46061J	33			YD158-YD170, YL955-YL999, YN236-YR328
0769		20		PA		9-0	23-11-21	C00857	A2	+		D46061J	33			YL951-YL954, YN231-YN235
0770		20		PA		8-11	23-11-21	C00857	B2	D		D46061J	32			YD158-YD170, YL955-YL999, YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W0040

Page 59

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description		From				To					
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0044	286A0044			P6 (LOAD WIRES) (continued)											
0770	20	PA			8-11	23-11-21	C00857	B2	+		D46061J	32			YL951-YL954, YN231-YN235
0771	20	PA			8-10	23-11-21	C00857	C2	D		D46061J	31			YD158-YD170, YL955-YL999, YN236-YR328
0771	20	PA			8-10	23-11-21	C00857	C2	+		D46061J	31			YL951-YL954, YN231-YN235
0772	22	CQ			8-10	23-27-31	C01500	=L	D		D46067J	13			YD158-YN235
0772	22	CQ			8-10	23-27-31	C01500	=L	+		D46067J	13			YN236-YR328
0824	24	B6			30-0	21-51-12	C01613	=L	D		D41828P	A03			YC053-YC059
0824	24	B6			9-7	21-51-12	C01613	=L	D		D40444J	16			YC065-YL999, YR301-YR328
0825	24	PK			30-0	21-51-22	C01614	=L	D		D41830P	B04			YC053-YC059
0825	24	PK			7-7	21-51-22	C01614	=L	D		D41832J	19			YC065-YL999, YR301-YR323, YR325-YR328
0850	20	GA			12-0	27-23-11	C01628	=L	D		D40526J	7			YC051-YD153
0850	20	PA			12-0	27-23-11	C01628	=L	D		D40352J	31			YD154-YD155
0850	20	PA			10-2	27-23-11	C01628	=L	D		D40352J	31			YD157-YR328
0851	20	GA			10-0	27-25-11	C01447	=L	D		SM00062		9		YC051-YD153
0851	20	PA			10-0	27-25-11	C01447	=L	D		SM00062		9		YD154-YD155
0851	20	PA			3-11	27-25-11	C01447	=L	D		SM00062		9		YD157-YR328
0852	20	GA			7-0	27-25-11	SM00062		9		D11939	A2			YC051-YD153
0852	20	PA			7-0	27-25-11	SM00062		9		D11939	A2			YD154-YD155
0852	20	PA			5-5	27-25-11	SM00062		9		D11939	A2			YD157-YR328
0853	20	PA			5-1	27-25-11	D11939	A1			D40352J	20			YD154-YR328
0854	20	GA			7-0	27-25-11	SM00062		9		D11939	X1			YC051-YD153
0854	20	PA			7-0	27-25-11	SM00062		9		D11939	X1			YD154-YD155
0854	20	PA			5-5	27-25-11	SM00062		9		D11939	X1			YD157-YR328
0855	20	PA			5-3	27-25-11	D11939	X2			D40368J	21			YD154-YR328
0856	20	GA			7-0	27-25-11	SM00062		9		D11941	A2			YC051-YD153
0856	20	PA			7-0	27-25-11	SM00062		9		D11941	A2			YD154-YD155
0856	20	PA			5-5	27-25-11	SM00062		9		D11941	A2			YD157-YR328
0857	20	PA			5-1	27-25-11	D11941	A1			D40352J	22			YD154-YR328
0858	20	GA			7-0	27-25-11	SM00062		9		D11941	X1			YC051-YD153
0858	20	PA			7-0	27-25-11	SM00062		9		D11941	X1			YD154-YD155
0858	20	PA			5-5	27-25-11	SM00062		9		D11941	X1			YD157-YR328
0859	20	PA			5-3	27-25-11	D11941	X2			D40368J	22			YD154-YR328
0866	20	PA			3-9	23-32-11	SM00065		9		D41832J	7			YL968-YL999

WIRE LIST

D280A108

91-21-11

Section W0040

Page 60

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0044	286A0044				P6 (LOAD WIRES) (continued)										
0867	20		PA	4-2	23-32-14	SM00065			9		D40750J	11			YD158-YN260
0882	20		GA	10-0	23-32-11	C01450	=L	D			D13712	C2			YC051-YC059
0882	20		PA	10-0	23-32-11	C01450	=L	D			D13712	C2			YC060-YD153
0882	20		PA	8-0	23-32-11	C01450	=L	D			D13712	C2			YD154-YN260
0883	20		PA	2-4	23-32-11	D13712		C1			SM00065		9		YD158-YN260
0884	20		PA	7-10	23-32-11	SM00065			9		D45233J	2			YD158-YN260
0886	20		GA	12-0	23-32-11	D13712		C1			D45233J	2			YC051-YD153
0886	20		PA	9-7	23-32-11	D13712		C1			D45233J	2			YD154-YD157
0888	16		CQ	8-6	31-62-11	D46063J		23			C01361	=L	D		ALL
0889	24		GK	9-0	24-28-41	C01627	=L	D			SM00066		9		YC051-YD153
0889	24		PK	7-3	24-28-41	C01627	=L	D			SM00066		9		YD154-YR328
0890	24		GK	7-0	24-28-41	SM00066			9		R00916	X1	C		YC051-YD153
0890	24		PK	5-1	24-28-41	SM00066			9		R00916	X1	C		YD154-YR328
0891	24		GK	11-0	24-28-41	R00916		X2	C		D13712	A1			YC051-YD153
0891	24		PK	8-9	24-28-41	R00916		X2	C		D13712	A1			YD154-YR328
0892	24		GK	4-0	24-28-41	SM00066			9		R00917	X1	C		YC051-YD153
0892	24		PK	1-9	24-28-41	SM00066			9		R00917	X1	C		YD154-YD158
0892	24		PK	1-10	24-28-41	SM00066			9		R00917	X1	C		YD160-YR328
0893	24		GK	7-0	24-28-41	R00917		X2	C		D13712	B1			YC051-YD153
0893	24		PK	4-11	24-28-41	R00917		X2	C		D13712	B1			YD154-YD158
0893	24		PK	5-0	24-28-41	R00917		X2	C		D13712	B1			YD160-YR328
0894	24		GK	5-0	24-28-41	SM00066			9		D13712	X1			YC051-YD153
0894	24		PK	3-5	24-28-41	SM00066			9		D13712	X1			YD154-YR328
0895	22		GA	10-0	24-28-41	D13712		X2			D40558J	14			YC051-YD153
0895	22		PA	7-9	24-28-41	D13712		X2			D40558J	14			YD154-YR328
0896	24		GK	26-0	24-28-41	D13712		A2			D40930P	A07			YC051-YD153
0896	24		PK	4-6	24-28-41	D13712		A2			D40352J	7			YD154-YR328
0897	24		GK	26-0	24-28-41	D13712		B2			D40930P	B07			YC051-YD153
0897	24		PK	4-6	24-28-41	D13712		B2			D40352J	25			YD154-YR328
0900	22		PA	10-2	52-51-11	C00137	=L	D			D13730	1			YD155-YR328
0901	22		PA	7-5	52-51-11	GD00638	DC..	1A			D13730	2			YD155-YR328
0902	20		GA	9-7	27-62-41	C01611	=L	D		*	D11839	A2			YC051-YC065
0902	22		PA	13-5	52-51-11	D40816J		5			D13730	3			YD155-YD158
0902	22		PA	12-4	52-51-11	D40816J		5			D13730	3			YD160-YR328
0903	20		GA	9-7	27-62-41	C01611	=L	D		*	D11839	X1			YC051-YC065
0903	22		PA	13-5	52-51-11	D40816J		6			D13730	4			YD155-YD158
0903	22		PA	12-4	52-51-11	D40816J		6			D13730	4			YD160-YR328
0904	20		GA	4-9	27-62-41	D46063J		11			D11839	X2			YC051-YC065
0904	22		PA	13-5	52-51-11	D40816J		8			D13730	5			YD155-YD158

WIRE LIST

D280A108

91-21-11

Section W0040

Page 61

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To						
Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0044	286A0044			P6 (LOAD WIRES) (continued)										
0904	22	PA		12-4	52-51-11	D40816J		8		D13730		5		YD160-YR328
0905	20	GA		2-2	27-62-41	D46063J		9		D40386J		23		YC051-YC052, YC058-YC065
0905	20	PA		2-2	27-62-41	D46063J		9		D40386J		23		YC053-YC057
0905	22	PA		13-5	52-51-11	D40816J		12		D13730		6		YD155-YD158
0905	22	PA		12-4	52-51-11	D40816J		12		D13730		6		YD160-YR328
0906	20	GA		2-2	27-62-41	D46063J		10		D40386J		24		YC051-YC065
0906	22	PA		7-5	52-51-11	GD00638	ST..	1A		D13730		7		YD155-YR328
0907	20	GA		4-11	27-62-41	D11839	A1			D40386J		29		YC051-YC065
0907	22	PA		7-5	52-51-11	GD00638	DC..	1A		D13730		8		YD155-YR328
0908	20	GA		4-11	27-62-41	D11839	A3			D40386J		9		YC051-YC065
0919	20	PA		7-1	21-31-23	C01271	=L	D		D40368J		23		YD158-YR328
0920	24	PK		5-5	21-31-23	D10824		7		D40368J		24		YD158-YR328
0921	20	GA		9-0	23-34-01	C01584	=L	D		D13712		D2		YC051-YC059
0921	20	PA		9-0	23-34-01	C01584	=L	D		D13712		D2		YC060-YD157
0921	20	PA		7-8	23-34-01	C01584	=L	D		D13712		D2		YD158-YN260
0922	20	GA		6-0	23-34-01	D13712	D1			D40800J		31		YC051-YC059
0922	20	PA		6-0	23-34-01	D13712	D1			D40800J		31		YC060-YD157
0922	20	PA		4-10	23-34-01	D13712	D1			D40800J		31		YD158-YN260
0926	20	PA		10-4	21-74-11	C01634	=L	D		D40218J		19		YD158-YD170
0927	14	PA		10-4	21-74-11	C01633	A1	D		D40218J		36	14	YD158-YD170
0928	14	PA		10-5	21-74-11	C01633	B1	D		D40218J		38	14	YD158-YD170
0929	14	PA		10-6	21-74-11	C01633	C1	D		D40218J		40	14	YD158-YD170
0930	20	PA		10-1	21-74-11	D13734	A1			D40218J		20		YD158-YD170
0931	20	PA		1-9	21-74-11	D13734	A2			GD00626	DC..	1A		YD158-YD170
0932	22	PA		4-0	21-74-11	D13734	X1			R00331	X1	C	*	YD158-YD170
0933	22	PA		4-1	21-74-11	D13734	X2			R00331	X2	C	*	YD158-YD170
0934	20	CQ		8-4	28-23-11	C01639	=L	D		D40750J		26		YD158
0934	20	CQ		8-4	28-23-11	C01659	=L	D		D40750J		26		YD160-YR328
0935	20	CQ		8-7	28-23-11	C01637	=L	D		D40750J		27		YD158-YR328
0936	20	CQ		8-11	28-23-11	D13790		15		D40750J		28		YD158-YR328
0937	20	CQ		2-10	28-23-11	D13790		1		GD00642	DC..	1A		YD158-YR328
0938	20	PA		8-4	28-23-11	C01640	=L	D		D40822J		15		YD158
0938	20	PA		8-4	28-23-11	C01658	=L	D		D40822J		15		YD160-YR328
0939	20	PA		8-8	28-23-11	C01638	=L	D		D40822J		23		YD158-YR328
0940	20	PA		9-0	28-23-11	D13792		14		D40822J		24		YD158-YR328
0941	20	PA		3-0	28-23-11	D13792		1		GD00638	DC..	1A		YD158-YR328
0955	20	PA		9-7	27-62-41	C01611	=L	D	*	D11839		A2		YN231-YN501
0956	20	PA		9-7	27-62-41	C01611	=L	D	*	D11839		X1		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W0040

Page 62

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0044		286A0044			P6 (LOAD WIRES) (continued)											
0957		20		PA		4-9	27-62-41	D46063J		16		D11839		X2		YN231-YN501
0958		20		PA		4-11	27-62-41	D11839		A1		D40386J		29		YN231-YN501
0959		20		PA		4-11	27-62-41	D11839		A3		D40386J		9		YN231-YN501
0960		20		PA		2-2	27-62-41	D46063J		17		D40386J		23		YN231-YN501
0961		20		PA		2-2	27-62-41	D46063J		18		D40386J		24		YN231-YN501
0996		20		PA		11-11	23-70-11	C01641	=L	D		D40218J		42		YL951-YR328
0997		20		PA		6-4	23-70-11	D40218J		43		GD00642	AC..	1A		YL951-YR328
0998		20		PA		8-0	23-32-21	C01670	=L	+		D40218J		12		YL951-YL967, YN231-YN235
1001R		22	X5	AA		11-10	26-11-11	C00405	=L	D		D40800J		9		YC051-YC057
1001R		22	X5	AA		11-9	26-11-11	C00405	=L	D		D40800J		9		YC058-YR328
1001Z				AA		0-0	26-11-11	C00405	DED			D40800J		DED		ALL
1002R		22	X5	AB		11-6	26-11-21	C00407	=L	D		D40812J		13		YC051-YC057
1002R		22	X5	AB		11-5	26-11-21	C00407	=L	D		D40812J		13		YC058-YR328
1002Z				AB		0-0	26-11-21	C00407	DED			D40812J		DED		ALL
1003R		22	X5	AC		11-7	26-11-21	C00396	=L	D		D40800J		10		YC051-YC057
1003R		22	X5	AC		11-6	26-11-21	C00396	=L	D		D40800J		10		YC058-YR328
1003Z				AC		0-0	26-11-21	C00396	DED			D40800J		DED		ALL
1004R		20		PH		11-5	26-11-31	C00403	=L	D		D40352J		1		YC051-YC057
1004R		20		PH		11-4	26-11-31	C00403	=L	D		D40352J		1		YC058-YR328
1005R		22	X5	AE		11-4	26-21-11	C01021	=L	D		D40812J		14		YC051-YC057
1005R		22	X5	AE		11-3	26-21-11	C01021	=L	D		D40812J		14		YC058-YR328
1005Z				AE		0-0	26-21-11	C01021	DED			D40812J		DED		ALL
1006R		22	X5	AF		11-3	26-21-11	C00297	=L	D		D40800J		11		YC051-YC057
1006R		22	X5	AF		11-2	26-21-11	C00297	=L	D		D40800J		11		YC058-YR328
1006Z				AF		0-0	26-21-11	C00297	DED			D40800J		DED		ALL
1007R		22	X5	AG		11-5	26-21-11	C01022	=L	D		D40800J		12		YC051-YC057
1007R		22	X5	AG		11-4	26-21-11	C01022	=L	D		D40800J		12		YC058-YR328
1007Z				AG		0-0	26-21-11	C01022	DED			D40800J		DED		ALL
1008R		22	X5	AH		11-1	26-21-11	C00452	=L	D		D40812J		15		YC051-YC057
1008R		22	X5	AH		11-0	26-21-11	C00452	=L	D		D40812J		15		YC058-YR328
1008Z				AH		0-0	26-21-11	C00452	DED			D40812J		DED		ALL
1009R		22	X5	AI		11-4	26-21-11	C00296	=L	D		D40800J		13		ALL
1009Z				AI		0-0	26-21-11	C00296	DED			D40800J		DED		ALL
1101		20	X1	BN		2-11	33-18-11	M00207	=C	\$		SM00014		9		YC053-YC057
1101		20	X1	BN		2-9	33-18-11	M00207	=C	\$		SM00014		9		YC058-YR328
1101Z				BN		0-0	33-18-11	M00207	DED			SM00014		DED		YC053-YR328
1102		20	X1	BP		6-3	33-18-11	M00208	=C	\$		SM00020		9		YC053-YR328
1102Z				BP		0-0	33-18-11	M00208	DED			SM00020		DED		YC053-YR328

WIRE LIST

D280A108

91-21-11

Section W0040

Page 63

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0044	286A0044				P6 (LOAD WIRES) (continued)										
1104	20	X1	BR		6-8	33-18-11	M00209	=C	\$		SM00026		9		YC053-YC057
1104	20	X1	BR		6-7	33-18-11	M00209	=C	\$		SM00026		9		YC058-YR328
1104Z			BR		0-0	33-18-11	M00209	DED			SM00026	DED			YC053-YR328
1105	20	X1	BS		5-3	33-18-11	M00210	=C	\$		SM00027		9		YC053-YC057
1105	20	X1	BS		5-5	33-18-11	M00210	=C	\$		SM00027		9		YC058-YR328
1105Z			BS		0-0	33-18-11	M00210	DED			SM00027	DED			YC053-YR328
1106	20	X1	BT		7-6	28-21-21	C01472	=L	D		R00669	=A	\$	*	YC053-YR323, YR325-YR328
1106Z			BT		0-0	28-21-21	C01472	DED			R00669	DED			YC053-YR328
1107	20	X1	BU		6-1	28-21-21	D12006	11			R00669	=A	\$	*	YC053-YR328
1107Z			BU		0-0	28-21-21	D12006	DED			R00669	DED			YC053-YR328
2001B	22	PB	GA		11-2	24-23-51	D40386J	18			D40226J	3			YC051-YC057, YC059-YR328
2001B	22	PB	GA		12-2	24-23-51	D40386J	18			D40226J	3			YC058
2001R	22	PB	GA		0-0	24-23-51	D40386J	20			D40226J	2			ALL
3001B	14	MZ	WA		9-10	27-41-12	C00840	C2	D		D40574J	4			YC051-YC057
3001B	14	MZ	WA		9-9	27-41-12	C00840	C2	D		D40574J	4			YC058-YR328
3001R	14	MZ	WA		0-0	27-41-12	C00840	A2	D		D40574J	5			ALL
3001Y	14	MZ	WA		0-0	27-41-12	C00840	B2	D		D40574J	6			ALL
5501	22	PA			10-6	27-62-11	C01663	=L	D		D40800J	36			YL953-YL999, YR301-YR328
5502	22	PA			8-2	27-62-11	C01662	=L	D		SM00069		9		YL953-YL999, YR301-YR328
5503	22	PA			2-11	27-62-11	SM00069		9		D40800J	33			YL953-YL999, YR301-YR328
5504	22	PA			2-11	27-62-11	SM00069		9		D40800J	32			YL953-YL999, YR301-YR328
6001	20	CQ			8-0	28-21-21	C00360	=B	D	*	C01344	=B	D		YC051-YC057
6001	20	CQ			7-11	28-21-21	C00360	=B	D	*	C01344	=B	D		YC058-YR328
6002	20	CQ			7-8	28-21-21	R00669	=C	F	*	C00359	=B	D	*	ALL
6003	20	CQ			1-1	28-21-21	C00359	=B	D	*	C00360	=B	D	*	ALL
6004	20	CQ			1-3	23-51-51	C00083	=B	D		C00085	=B	D		ALL
6005	20	CQ			1-3	23-51-51	C00086	=B	D		C00084	=B	D		ALL
6048	22	PA			9-2	46-11-51	C01694	=L	+		D40820J	4			YL951-YL954, YN231-YN235
6087	20	PA			6-1	23-32-11	SM00065		9		D40532J	15			YN236-YN260
6201	18	CQ			6-4	24-61-61	C03064	=L	D		D11756	A3			ALL
6202	18	CQ			4-11	24-61-61	D11756	A2			TB5060C	2	E		YC051-YC061
6202	18	CQ			4-11	24-61-61	D11756	A2			TB5060C	9	E		YC062-YR328

WIRE LIST

D280A108

91-21-11
Section W0040
Page 64
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W0044	286A0044	P6 (LOAD WIRES) (continued)			
6203	18 CQ	6-5 24-61-61	C03065 =L D	D11756 A1	ALL
A-AA		0-0 33-14-12	L00274 =P	D40744P =1 VG	ALL
A-AB		0-0 33-14-12	L00274 =G	GD00628 DC.. E	ALL
A-AE		0-0 23-51-51	C00083 =B D	M00542 BLU	ALL
A-AG		0-0 33-17-11	GD00618 AC.. E	L00012 =G	ALL
A-AH		0-0 33-17-11	L00012 =P	TB5060J 1 E	ALL
A-BE		0-0 23-51-51	M00542 RED	C00239 =L D	ALL
B-AA		0-0 23-51-51	C00086 =B D	M00544 BLU	ALL
B-BB		0-0 23-51-51	M00544 RED	C00560 =L D	ALL
C-AA		0-0 23-51-51	C00085 =B D	M00543 BLU	ALL
C-BA		0-0 23-51-51	M00543 RED	C00240 =L D	ALL
D-AA		0-0 23-51-51	C00084 =B D	M00545 BLU	ALL
D-BA		0-0 23-51-51	M00545 RED	C00561 =L D	ALL
PA01		0-0 33-18-11	D01614 G2	D01614 G3	ALL
PA03		0-0 33-18-11	D01616 G2	D01616 G3	ALL
PA04		0-0 33-18-11	D01618 G2	D01618 G3	ALL
W0048	286A0048	P19 (EXTERNAL POWER RECEPTACLE PANEL)			
0008	20 PA	1-1 33-32-11	D44252J 9	S00063 1 C	YC051-YL954, YN231-YN235
0008	20 PA	1-8 33-32-11	D40665 18	S00063 1 C	YL955-YL999, YN236-YR328
0009	20 PA	1-0 33-32-11	D44252J 11	S00063 2 C	YC051-YL954, YN231-YN235
0009	20 PA	1-7 33-32-11	D40665 11	S00063 2 C	YL955-YL999, YN236-YR328
0010	20 PA	1-0 33-32-11	D44252J 10	S00063 3 C	YC051-YL954, YN231-YN235
0010	20 PA	1-7 33-32-11	D40665 20	S00063 3 C	YL955-YL999, YN236-YR328
0503	22 PA	1-8 24-41-11	D44252J 3	L00348 =G Z	YC051-YL954, YN231-YN235
0503	22 PA	1-6 24-41-11	D40665 27	L00348 =G Z	YL955-YL999, YN236-YR328
0504	22 PA	1-8 24-41-11	D44252J 4	L00348 =P Z	YC051-YL954, YN231-YN235
0504	22 PA	1-6 24-41-11	D40665 4	L00348 =P Z	YL955-YL999, YN236-YR328
0505	22 PA	1-8 32-44-11	L01002 =G Z1	D44252J 13	YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0040

Page 65

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0048	286A0048				P19 (EXTERNAL POWER RECEPTACLE PANEL) (continued)										
0506	24	PK			1-8	32-44-11	L01002	= P	Z1		D44252J	12			YC051-YD157
2201B	22	PB	A		1-10	24-41-11	D04499J	4			L00349	= P	Z		YC051-YL954, YN231-YN235
2201B	22	PB	A		1-7	24-41-11	D40665	25			L00349	= P	Z		YL955-YL999, YN236-YR328
2201R	22	PB	A		0-0	24-41-11	D04499J	3			L00349	= G	Z		YC051-YL954, YN231-YN235
2201R	22	PB	A		0-0	24-41-11	D40665	26			L00349	= G	Z		YL955-YL999, YN236-YR328
8001	20	PA			1-4	23-43-11	D44252J	6			S00033	= A	C		YC051-YL954, YN231-YN235
8001	20	PA			1-11	23-43-11	D40665	19			S00033	= A	C		YL955-YL999, YN236-YR328
8002	20	PA			1-5	23-42-11	D44252J	7			S00033	= B	C	*	YC051-YD157
8003	20	PA			1-3	23-43-11	D44252J	5			S00033	= C	C		YC051-YL954, YN231-YN235
8003	20	PA			1-10	23-43-11	D40665	22			S00033	= C	C		YL955-YL999, YN236-YR328
8004	20	PA			1-5	23-42-11	D44252J	8			S00033	= B	C	*	YC051-YD157
8004	20	PA			1-5	23-43-11	D44252J	8			S00033	= B	C		YD158-YL954, YN231-YN235
8004	20	PA			2-0	23-43-11	D40665	8			S00033	= B	C		YL955-YL999, YN236-YR328
A-BK				YA	0-0	23-41-11	D06009	BLK			D04499J	9			YC051-YL954, YN231-YN235
A-BK				YA	0-0	23-41-11	D06009	BLK			D40665	30			YL955-YL999, YN236-YR328
A-BL				YA	0-0	23-41-11	D06009	BLU			D04499J	8			YC051-YL954, YN231-YN235
A-BL				YA	0-0	23-41-11	D06009	BLU			D40665	29			YL955-YL999, YN236-YR328
A-RD				YA	0-0	23-41-11	D06009	RED			D04499J	7			YC051-YL954, YN231-YN235
A-RD				YA	0-0	23-41-11	D06009	RED			D40665	28			YL955-YL999, YN236-YR328
B-BK				YB	0-0	23-41-11	D04499J	12			D06007	BLK			YD158-YL954, YN231-YN235
B-BK				YB	0-0	23-41-11	D40665	33			D06007	BLK			YL955-YL999, YN236-YR328

WIRE LIST
D280A108

91-21-11
Section W0040
Page 66
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0048	286A0048			P19 (EXTERNAL POWER RECEPTACLE PANEL) (continued)											
B-BL				YB	0-0	23-41-11	D04499J	11			D06007		BLU		YD158-YL954, YN231-YN235
B-BL				YB	0-0	23-41-11	D40665	32			D06007		BLU		YL955-YL999, YN236-YR328
B-RD				YB	0-0	23-41-11	D04499J	10			D06007		RED		YD158-YL954, YN231-YN235
B-RD				YB	0-0	23-41-11	D40665	31			D06007		RED		YL955-YL999, YN236-YR328
W0049	286A0049			THRUST LEVER ENGINE NO. 1											
0001	22		GA		3-0	22-11-14	D08313J	1			S00786A		C	\$	ALL
0002	22		GA		3-0	22-11-14	D08313J	2			S00786A		NO	\$	ALL
0003	22		GA		3-0	22-11-14	D08313J	11			S00787A		C	\$	ALL
0004	22		GA		3-0	22-11-14	D08313J	12			S00787A		NO	\$	ALL
0005	22		GA		3-0	22-31-51	D08313J	5			S00113		2	A	ALL
0006	22		GA		3-0	22-31-51	D08313J	6			S00113		3	A	ALL
0007	22		GA		3-0	22-31-51	D08313J	7			S00113		4	A	ALL
0008	22		GA		3-0	22-31-51	D08313J	8			S00113		1	A	ALL
0011	22		GA		3-0	78-34-11	D10171J	1			S00828		NC	\$	ALL
0014	22		GA		3-0	78-34-11	D10171J	4			S00828		C	\$	ALL
0015	22		GA		3-0	78-34-11	D10171J	5			S00828		NO	\$	ALL

WIRE LIST

D280A108

91-21-11

Section W0040

Page 67 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Diagram	From				To				
	Wire No.	GA	CO TY	Fam		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I	W0050	286A0050			FWD ENTRY LIGHT MODULE (M01677)									
I	0001	20	PA		2-5	33-29-11	D10754		1	D10760		A		YC051-YN260
I	0002	20	PA		2-5	33-29-11	D10754		2	D10760		G		YC051-YN260
I	0003	22	PA		2-5	33-29-11	D10754		3	D10760		D		YC051-YN260
I	0004	20	PA		1-10	33-29-11	D10754		4	GD00150	ST..	E		YC051-YN260
I	0005	20	PA		1-7	33-29-11	D10754		5	L01287	=P	I		YC051-YN260
I	0006	20	PA		1-7	33-29-11	D10754		6	L01287	=G	G		YC051-YN260
I	0007	20	PA		2-5	33-29-11	D10754		7	D10760		F		YC051-YN260
I	0008	22	PA		2-5	33-29-11	D10754		8	D10760		E		YC051-YN260
I	0009	20	PA		1-7	33-29-11	GD00150	ST..	E	D10760		H		YC051-YN260
I	0010	20	PA		1-4	33-29-11	SP03504		S	D10760		M		YC051-YN260
I	0011	20	PA		1-4	33-29-11	SP03506		S	D10760		L		YC051-YN260
I	A-A				0-0	33-29-11	L01288	=A		D10760		J		YC051-YN260
I	A-B				0-0	33-29-11	L01288	=B		D10760		K		YC051-YN260
I	A-C				0-0	33-29-11	L01288	=C		SP03504			S	YC051-YN260
I	A-D				0-0	33-29-11	L01288	=D		SP03506			S	YC051-YN260
I	A-E				0-0	33-29-11	L01289	=A		D10760		C		YC051-YN260
I	A-F				0-0	33-29-11	L01289	=B		D10760		B		YC051-YN260
I	A-G				0-0	33-29-11	L01289	=C		SP03506			S	YC051-YN260
I	A-H				0-0	33-29-11	L01289	=D		SP03504			S	YC051-YN260
I	W0051	286A0051			TITLE THRUST LEVER ENGINE NO. 2									
I	0001	22	GA		3-0	22-11-14	D08315J		1	S00786B		C	\$	ALL
I	0002	22	GA		3-0	22-11-14	D08315J		2	S00786B		NO	\$	ALL
I	0003	22	GA		3-0	22-11-14	D08315J		11	S00787B		C	\$	ALL
I	0004	22	GA		3-0	22-11-14	D08315J		12	S00787B		NO	\$	ALL
I	0005	22	GA		3-0	22-31-51	D08315J		5	S00114		2	A	ALL
I	0006	22	GA		3-0	22-31-51	D08315J		6	S00114		3	A	ALL
I	0007	22	GA		3-0	22-31-51	D08315J		7	S00114		4	A	ALL
I	0008	22	GA		3-0	22-31-51	D08315J		8	S00114		1	A	ALL
I	0031	22	GA		3-0	78-34-21	D10173J		1	S00829		NC	\$	ALL
I	0034	22	GA		3-0	78-34-21	D10173J		4	S00829		C	\$	ALL
I	0036	22	GA		3-0	78-34-21	D10173J		5	S00829		NO	\$	ALL
I	W0052	286A0052			AFT ENTRY LIGHT MODULE (M01678)									
I	0001	20	PA		1-7	33-29-11	D11462		1	D11464		A		YC051-YN260
I	0002	20	PA		1-7	33-29-11	D11462		2	D11464		G		YC051-YN260
I	0003	22	PA		1-7	33-29-11	D11462		3	D11464		D		YC051-YN260
I	0004	20	PA		2-5	33-29-11	D11462		4	GD00152	ST..	E		YC051-YN260
I	0005	20	PA		2-2	33-29-11	D11462		5	L01306	=P	I		YC051-YN260

WIRE LIST

D280A108

91-21-11

Section W0050

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY	Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice Effectivity
W0052	286A0052	AFT ENTRY LIGHT MODULE (M01678) (continued)			
0006	20	PA	2-3 33-29-11	D11462 6	L01306 =G G YC051-YN260
0007	20	PA	1-7 33-29-11	D11462 7	D11464 F YC051-YN260
0008	22	PA	1-7 33-29-11	D11462 8	D11464 E YC051-YN260
0009	20	PA	2-4 33-29-11	GD00152 ST.. E	D11464 H YC051-YN260
0010	20	PA	2-11 33-29-11	SP03508 S	D11464 M YC051-YN260
0011	20	PA	2-9 33-29-11	SP03512 S	D11464 L YC051-YN260
A-A			0-0 33-29-11	L01304 =A	D11464 J YC051-YN260
A-B			0-0 33-29-11	L01304 =B	D11464 K YC051-YN260
A-C			0-0 33-29-11	L01304 =C	SP03508 S YC051-YN260
A-D			0-0 33-29-11	L01304 =D	SP03512 S YC051-YN260
A-E			0-0 33-29-11	L01305 =A	D11464 C YC051-YN260
A-F			0-0 33-29-11	L01305 =B	D11464 B YC051-YN260
A-G			0-0 33-29-11	L01305 =C	SP03512 S YC051-YN260
A-H			0-0 33-29-11	L01305 =D	SP03508 S YC051-YN260
W0054	286A0054	P6B (LOAD WIRES)			
0001	22	CQ	13-5 31-53-11	C01698 =L D	D46061J 5 YC060-YC064
0001	22	CQ	11-7 31-53-11	C01698 =L D	D46061J 20 YL953-YL999, YN233-YN260
0001	22	CQ	11-9 31-53-11	C01698 =L D	D46061J 20 YN501-YR324
0018	22	PA	9-1 23-42-14	C01936 =L D	D40226J 20 YN501-YR324
0019	24	PK	9-7 23-42-14	D02879 25	D40708J 12 YN501-YR324
0020	20	PA	2-5 23-42-14	D02879	GD00061 ST.. E YN501-YR324
0021	22	PA	13-6 33-51-11	C01949 =L D	D40226J 19 YN501-YR324
0022	20	PA	12-4 44-21-10	C01952 =L D	D13712 D2 YN501-YR324
0679	20	PA	5-5 44-21-36	D45233J 4	GD00642 AC.. 1A YN501-YR324
0681	20	PA	5-5 44-21-46	D45233J 6	GD00642 AC.. 1A YN501-YR324
0683	20	PA	5-5 44-21-37	D45233J 8	GD00642 AC.. 1A YN501-YR324
0685	20	PA	5-5 44-21-47	D45233J 10	GD00642 AC.. 1A YN501-YR324
0867	20	PA	3-5 44-21-22	SM00065 9	D40750J 11 YN501-YR324
0967	20	PA	1-5 44-21-10	D13840 D1	SM00065 9 YN501-YR324
0968	20	PA	4-1 44-21-10	D13840 D2	D40708J 5 YN501-YR324
0971	20	PA	12-5 44-21-10	C01945 =L D	D13840 A1 YN501-YR324
0973	20	PA	1-4 44-21-10	D13712 D1	SM00065 9 YN501-YR324
0974	20	PA	3-11 44-21-10	SM00065 9	D40822J 22 YN501-YR324
0975	24	PK	1-3 44-21-36	D12215 X1	SM00065 9 YN501-YR324
0976	24	PK	1-3 44-21-36	D12215 X2	SM00068 9 YN501-YR324
0977	20	PA	12-3 44-21-36	C01452 =L D	D12215 A2 YN501-YR324
0978	20	PA	10-5 44-21-36	D12215 A1	D45233J 3 YN501-YR324

WIRE LIST

D280A108

91-21-11

Section W0050

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0054		286A0054			P6B (LOAD WIRES) (continued)											
0979		20		PA		12-2	44-21-46	C01453	=L	D		D12215	B2			YN501-YR324
0980		20		PA		10-5	44-21-46	D12215	B1			D45233J	5			YN501-YR324
0981		20		PA		12-1	44-21-37	C01454	=L	D		D12215	C2			YN501-YR324
0982		20		PA		10-5	44-21-37	D12215	C1			D45233J	7			YN501-YR324
0983		20		PA		12-0	44-21-47	C01455	=L	D		D12215	D2			YN501-YR324
0984		20		PA		10-5	44-21-47	D12215	D1			D45233J	9			YN501-YR324
0985		20		PA		1-5	44-21-10	D13840	X1			SM00065		9		YN501-YR324
0986		20		PA		1-5	44-21-10	D13840	X2			SM00068		9		YN501-YR324
0987		20		PA		3-11	44-21-10	SM00068			9	D40822J	21			YN501-YR324
0988		20		PA		4-1	44-21-10	D13840	A2			D40708J	17			YN501-YR324
2011B		24		Y2	AD	7-3	23-42-14	SP00845		S		D40708J	6			YN501-YR301
2011B		24		Y2	AD	6-8	23-42-14	TB0610Y	B021	1A		D40708J	6			YR303-YR324
2011R		24		Y2	AD	0-0	23-42-14	SP00843		S		D40708J	1			YN501-YR301
2011R		24		Y2	AD	0-0	23-42-14	TB0610Y	A021	1A		D40708J	1			YR303-YR324
2011Z					AD	0-0	23-42-14	SP00847		S		D40708J			AC	YN501-YR301
2011Z					AD	0-0	23-42-14	GB00610	ST..	1A		D40708J			AC	YR303-YR324
2012B		24		Y2	AC	9-7	23-42-14	D02879		43		D40708J	11			YN501-YR324
2012R		24		Y2	AC	0-0	23-42-14	D02879		42		D40708J	4			YN501-YR324
2012Z					AC	0-0	23-42-14	D02879			AB	D40708J			AC	YN501-YR324
FRAA						0-0	23-42-14	D40708J			AC	D40708J	21			YN501-YR324

WIRE LIST

D280A108

91-21-11
Section W0050
Page 3 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0063	286A0063			NITROGEN GEN SYS - OPERABILITY INDICATOR											
1001	20	VF	AA		1-3	47-30-11	L01462	-	B	*	D14112	5			YD160-YR328
1001Z			AA		0-0	47-30-11	GD06310	ST..	1		D14112	PERB			YD160-YR328
1002	20	VF	AB		1-3	47-30-11	L01462	+	B		D14112	1			YD160-YR328
1002Z			AB		0-0	47-30-11	GD06310	ST..	1		D14112	PERB			YD160-YR328
1003	20	VF	AC		1-4	47-30-11	L01463	+	B		D14112	2			YD160-YR328
1003Z			AC		0-0	47-30-11	GD06310	ST..	1		D14112	PERB			YD160-YR328
1004	20	VF	AD		1-6	47-30-11	L01464	+	B		D14112	3			YD160-YR328
1004Z			AD		0-0	47-30-11	GD06310	ST..	1		D14112	PERB			YD160-YR328
1005	20	VF	AE		1-1	47-30-11	L01462	-	B	*	L01463	-	B	*	YD160-YR328
1005Z			AE		0-0	47-30-11	GD06310	ST..	1		GD06310	ST..	1		YD160-YR328
1006	20	VF	AF		1-0	47-30-11	L01463	-	B	*	L01464	-	B		YD160-YR328
1006Z			AF		0-0	47-30-11	GD06310	ST..	1		GD06310	ST..	1		YD160-YR328
W0066	286A0066			J46 INTEGRATION PANEL WIRING											
0001	24	PK			2-1	21-25-11	D46108J	1			TB0660Y	A001	1A		ALL
0002	24	PK			2-8	21-25-11	D46128J	A01			TB0660Y	A001	1A		ALL
0003	24	PK			2-0	21-25-11	D46102J	17			TB0660Y	A001	1A		ALL
0004	22	PA			1-6	21-25-11	D46108J	2			D46116J	15			YC051-YL999, YR301-YR328 YN231-YN501
0004	22	PA			1-6	SPARE	D46108J	2			D46116J	15			YN231-YN501
0005	22	PA			1-9	21-27-21	D46114J	1			D46102J	2			ALL
0006	22	PA			2-0	21-27-21	D46102J	3			D46142J	A01			ALL
0007	22	G5			1-11	21-27-31	D46112J	1			D46116J	28			ALL
0008	22	PA			2-3	21-27-31	D46100J	6			D46130J	A01			ALL
0009	22	G5			2-1	21-27-31	D46116J	29			D46138J	A01			ALL
0011	22	G5			2-7	21-27-31	D46138J	A02			TB0660Y	A005	1A		ALL
0012	22	G5			2-2	21-27-31	D46104J	1			TB0660Y	A005	1A		ALL
0013	22	G5			2-0	21-27-31	D46116J	16			TB0660Y	A005	1A		ALL
0014	22	G5			2-3	21-27-31	D46112J	2			TB0664Y	A001	1A		ALL
0015	22	G5			2-2	21-27-31	D46100J	31			TB0664Y	A001	1A		ALL
0016	22	G5			2-5	21-27-31	D46138J	A03			TB0664Y	A001	1A		ALL
0017	22	PA			2-1	21-33-11	D46108J	3			TB0660Y	B001	1A		YC051-YC059, YC065-YL951, YN231 YC060-YC064 YL952-YL999, YN232-YR328 YC051-YC059, YC065-YL951, YN231 YC060-YC064
0017	22	CQ			3-0	21-33-11	D46108J	3			TB0662Y	B019	1A		YC060-YC064
0017	22	CQ			1-9	21-33-11	D46108J	3			TB0662Y	B019	1A		YL952-YL999, YN232-YR328 YC051-YC059, YC065-YL951, YN231 YC060-YC064
0018	22	PA			2-3	21-33-11	D46104J	2			TB0660Y	B001	1A		YC051-YC059, YC065-YL951, YN231 YC060-YC064
0018	22	CQ			3-0	21-33-11	D46104J	2			TB0662Y	A019	1A		YC060-YC064

WIRE LIST

D280A108

91-21-11

Section W0060

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0066	286A0066				J46 INTEGRATION PANEL WIRING (continued)										
0018	22		CQ		1-11	21-33-11	D46104J		2		TB0662Y	A019	1A		YL952-YL999, YN232-YR328
0019	22		PA		2-1	21-33-11	D46108J		4		TB0660Y	A003	1A		YC051-YC059, YC065-YD158
0019	22		CQ		4-0	21-33-11	D46108J		4		TB0660Y	A003	1A		YC060-YC064
0019	22		PA		2-2	21-33-11	D46108J		4		TB0664Z	A021	1A		YL951, YN231
0019	22		CQ		2-2	21-33-11	D46108J		4		TB0664Z	A021	1A		YL952-YL999, YN232-YR328
0020	22		PA		2-3	21-33-11	D46104J		3		TB0660Y	A003	1A		YC051-YC059, YC065-YD158
0020	22		CQ		4-0	21-33-11	D46104J		3		TB0660Y	A003	1A		YC060-YC064
0020	22		PA		2-3	21-33-11	D46104J		3		TB0664Z	A021	1A		YL951, YN231
0020	22		CQ		2-3	21-33-11	D46104J		3		TB0664Z	A021	1A		YL952-YL999, YN232-YR328
0021	24		B6		2-0	21-43-21	D46108J		5		TB0660Y	A009	1A		ALL
0022	24		B6		2-6	21-43-21	D46128J		A02		TB0660Y	A009	1A		ALL
0023	24		B6		2-6	21-43-21	D46120J		A02		TB0660Y	A009	1A		ALL
0024	24		G6		2-1	21-51-11	D46108J		8		D46120J	A10			ALL
0025	24		B6		2-1	21-43-21	D46108J		6		D46120J	B02			YC051-YD158
0026	24		B6		2-1	21-43-21	D46108J		7		D46120J	A03			YC051-YD158
0027	24		B6		1-10	21-43-21	D46126J		2		D46120J	B03			ALL
0028	22		PA		2-1	31-31-15	D46122J		1		TB0660Y	A003	1A		YC051-YD158
0028	22		PA		2-1	31-31-15	D46122J		1		TB0664Z	A021	1A		YL951-YR328
0029	20		CQ		2-1	31-52-11	D46104J		4		TB0660Y	B009	1A		ALL
0030	20		CQ		2-0	31-52-11	D46104J		5		TB0660Z	A013	1A		ALL
0031	20		CQ		2-0	31-52-75	D46108J		25		TB0660Y	B009	1A		ALL
0032	20		CQ		2-0	31-52-51	D46108J		16		TB0660Y	B009	1A		YC051-YL999, YR301-YR328
0032	20		CQ		2-0	SPARE	D46108J		16		TB0660Y	B009	1A		YN231-YN501
0033	20		CQ		2-1	31-52-21	D46104J		6		TB0660Y	A011	1A		ALL
0034	20		CQ		2-1	31-52-21	D46104J		7		TB0660Y	A011	1A		ALL
0035	20		CQ		2-0	31-52-21	D46108J		9		TB0660Y	A011	1A		ALL
0036	20		CQ		1-11	31-52-21	D46108J		10		TB0660Z	A013	1A		ALL
0037	20		CQ		2-0	31-52-25	D46108J		12		TB0660Y	B009	1A		ALL
0038	20		CQ		2-0	31-52-25	D46108J		11		TB0660Y	B011	1A		ALL
0039	20		CQ		2-1	31-52-25	D46104J		8		TB0660Y	B011	1A		ALL
0040	20		CQ		2-1	31-52-25	D46104J		9		TB0660Y	B011	1A		ALL
0041	20		CQ		2-2	31-52-31	D46104J		10		TB0660Y	B005	1A		ALL
0042	20		CQ		2-2	31-52-31	D46104J		11		TB0660Y	B005	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0060

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0066		286A0066				J46 INTEGRATION PANEL WIRING (continued)									
	0043	20	CQ		2-1	31-52-31	D46108J		13		TB0660Y	B005	1A		ALL
	0044	20	CQ		2-1	31-52-35	D46108J		14		TB0660Y	A007	1A		ALL
	0045	20	CQ		2-2	31-52-35	D46104J		12		TB0660Y	A007	1A		ALL
	0046	20	CQ		2-2	31-52-35	D46104J		13		TB0660Y	A007	1A		ALL
	0047	20	CQ		2-2	31-52-41	D46126J		4		TB0660Y	B007	1A		ALL
	0048	20	CQ		2-2	31-52-41	D46104J		14		TB0660Y	B007	1A		ALL
	0049	20	CQ		2-2	31-52-41	D46104J		15		TB0660Y	B007	1A		ALL
	0050	20	CQ		2-6	31-52-45	D46128J	A04			TB0660Z	A013	1A		ALL
	0051	20	CQ		1-11	31-52-51	D46108J		15		TB0660Y	A017	1A		ALL
	0052	20	CQ		2-0	31-52-51	D46104J		16		TB0660Y	A017	1A		ALL
	0053	20	CQ		2-0	31-52-51	D46104J		17		TB0660Y	A017	1A		ALL
	0054	20	CQ		1-11	31-52-61	D46108J		18		TB0660Y	B017	1A		ALL
	0055	20	CQ		2-0	31-52-61	D46104J		20		TB0660Y	B017	1A		ALL
	0056	20	CQ		2-0	31-52-61	D46104J		21		TB0660Y	B017	1A		ALL
	0057	20	CQ		1-11	31-52-65	D46108J		19		TB0660Y	A019	1A		ALL
	0058	20	CQ		2-0	31-52-65	D46104J		22		TB0660Y	A019	1A		ALL
	0059	20	CQ		2-0	31-52-65	D46104J		33		TB0660Y	A019	1A		ALL
	0060	20	CQ		2-0	31-52-71	D46104J		24		TB0660Z	A013	1A		ALL
	0061	20	CQ		1-11	31-52-55	D46108J		17		TB0660Y	B019	1A		ALL
	0062	20	CQ		2-0	31-52-55	D46104J		18		TB0660Y	B019	1A		ALL
	0063	20	CQ		2-0	31-52-55	D46104J		19		TB0660Y	B019	1A		ALL
	0064	20	CQ		2-1	31-52-75	D46104J		25		TB0660Y	A021	1A		ALL
	0065	20	CQ		2-1	31-52-75	D46104J		26		TB0660Y	A021	1A		ALL
	0066	20	CQ		2-0	31-52-75	D46108J		20		TB0660Y	A021	1A		ALL
	0067	22	PA		1-7	31-53-11	D46104J		27		D46116J	17			ALL
	0068	22	PA		2-1	31-53-11	D46116J		5		TB0660Y	B001	1A		YC051-YC059, YC065-YD158 YC060-YC064 YL951-YR328
	0068	22	CQ		3-0	31-53-11	D46116J		5		TB0662Y	A019	1A		YC060-YC064 YL951-YR328
	0068	22	CQ		1-10	31-53-11	D46116J		5		SM00005		W		ALL
	0069	22	PA		2-0	31-53-11	D46116J		6		D46110J	A05			ALL
	0070	22	PA		2-0	31-53-11	D46116J		1		D46130J	A02			ALL
	0071	22	PA		1-9	31-53-11	D46102J		4		D46106J	7			ALL
	0072	20	CQ		2-6	33-18-11	D46120J	B04			TB0660Y	B021	1A		ALL
	0073	20	CQ		2-6	33-18-11	D46120J	A04			TB0660Y	B021	1A		ALL
	0074	20	CQ		2-0	33-18-11	D46116J		30		TB0660Y	B021	1A		ALL
	0075	22	PA		1-9	23-34-01	D46102J		18		D46100J	8			YC051-YN260
	0075	22	PA		1-9	44-21-26	D46102J		18		D46100J	8			YN501-YR328
	0076	22	PA		1-9	23-34-01	D46102J		19		D46100J	7			YC051-YC052
	0076	22	GA		1-9	23-34-01	D46102J		19		D46100J	7			YC053-YC059

WIRE LIST

D280A108

91-21-11

Section W0060

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0066	286A0066				J46 INTEGRATION PANEL WIRING (continued)										
0076	22		PA		2-1	23-34-01	TB0662Y	B013	1A		D46100J	7			YC060-YN260
0076	22		PA		1-9	44-21-26	D46102J	21			D46100J	25			YN501-YR328
0077	18		CQ		1-7	24-11-21	D46126J	21			D46100J	21			ALL
0079	22		PA		2-1	24-22-21	D46114J	2			D46142J	A02			ALL
0080	22		PA		2-1	24-28-11	D46142J	A03			D46114J	3			ALL
0081	22		PA		2-1	24-28-11	D46142J	A04			D46114J	4			ALL
0082	22		PA		2-0	SPARE	D46138J	A04			D46102J	20			ALL
0083	22		PA		2-1	SPARE	D46138J	A05			D46100J	9			ALL
0084	20		PA		1-7	27-41-12	D46150J	1			D46122J	25			ALL
0085	22		PA		1-11	27-62-21	D46110J	A03			D46102J	26			ALL
0086	22		PA		1-11	27-62-21	D46110J	B03			D46102J	27			YC051-YL952, YN231-YN501
0086	22		PA		2-9	27-62-21	D46110J	B03			TB0664Y	B003	1A		YL953-YL999, YR301-YR328
0087	20		CQ		1-10	28-21-11	D46132J	A04			D46126J	8			ALL
0088	20		CQ		2-6	28-21-11	D46120J	A05			TB0660Y	A023	1A		ALL
0089	20		CQ		2-1	28-21-11	D46126J	1			TB0660Y	A023	1A		ALL
0090	20		CQ		2-6	28-21-11	D46132J	A03			TB0660Y	A023	1A		ALL
0091	20		PA		1-10	28-42-11	D46114J	5			D46122J	27			ALL
0092	20		PA		1-10	28-42-11	D46114J	6			D46122J	28			ALL
0093	20		CQ		2-2	29-11-11	D46132J	A01			D46120J	A01			ALL
0094	20		CQ		2-2	29-11-11	D46132J	A02			D46120J	B01			ALL
0095	22		G5		2-0	29-11-12	D46138J	A06			D46124J	A01			ALL
0096	22		G5		2-0	29-11-12	D46138J	A07			D46124J	A02			ALL
0097	22		CQ		2-5	29-22-11	D46142J	A05			D46124J	A03			ALL
0098	22		G5		2-0	29-23-11	D46110J	B02			D46116J	27			ALL
0099	22		G5		2-5	29-23-11	D46128J	A03			D46100J	32			ALL
0101	22		G5		2-0	29-25-11	D46110J	A01			D46116J	13			ALL
0102	22		G5		2-4	29-25-11	D46110J	B01			D46100J	33			ALL
0103	24		PK		1-9	29-33-11	D46106J	3			D46102J	1			ALL
0104	24		G6		1-7	29-33-11	D46126J	3			D46106J	4			ALL
0105	20		PA		2-2	30-21-21	D46114J	7			D46144J	A01			ALL
0106	20		PA		2-2	30-21-21	D46114J	10			D46144J	A04			ALL
0107	22		G5		1-8	30-31-12	D46112J	3			D40097J	A01			ALL
0108	22		G5		1-8	30-31-12	D46112J	4			D40097J	A02			ALL
0109	22		G5		1-8	30-31-12	D46112J	5			D40097J	A03			ALL
0110	22		PA		2-4	23-34-01	D46128J	B10			TB0662Y	B013	1A		YC060-YN260
0110	20		PA		1-9	44-21-26	D46102J	35			D46100J	17			YN501-YR328
0111	24		PK		2-4	32-41-11	D46100J	2			TB0662Y	A001	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0060

Page 4

Nov 12/2012

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0066	286A0066			J46 INTEGRATION PANEL WIRING (continued)											
0112	24		PK		2-4	32-41-11	D46100J		10		TB0662Y	A001	1A		ALL
0113	24		PK		2-4	32-41-11	D46100J		1		TB0662Y	A001	1A		ALL
0114	22		PA		1-11	32-42-11	D46110J		A04		D46102J		28		ALL
0115	22		PA		1-11	32-42-11	D46110J		B04		D46102J		29		ALL
0116	22		PA		1-11	32-44-11	D46100J		11		D46104J		29		ALL
0117	22		PA		1-8	23-34-01	D46102J		19		TB0662Y	B013	1A		YC060-YN260
0118	22		PA		2-4	32-44-11	D46100J		12		TB0662Y	B001	1A		ALL
0119	22		PA		2-2	32-44-11	D46104J		28		TB0662Y	B001	1A		ALL
0120	22		PA		2-2	32-44-11	D46104J		30		TB0662Y	B001	1A		ALL
0121	22		PA		1-11	32-44-11	D46100J		13		D46104J		31		ALL
0123	24		PK		1-9	32-64-12	D46114J		11		D46102J		7		ALL
0124	24		PK		1-9	32-64-12	D46114J		12		D46102J		8		ALL
0125	24		PK		1-9	32-64-12	D46114J		13		D46102J		9		ALL
0126	24		PK		1-10	23-31-06	D46122J		21		D46114J		21		YD158-YN260
0126	24		PK		1-10	44-21-22	D46122J		21		D46114J		21		YN501-YR328
0127	24		PK		1-10	23-31-06	D46122J		22		D46114J		22		YD158-YN260
0127	24		PK		1-10	44-21-22	D46122J		22		D46114J		22		YN501-YR328
0128	20		G5		2-1	32-64-21	D46108J		21		TB0660Y	B003	1A		ALL
0129	20		G5		2-1	32-64-21	D46116J		3		TB0660Y	B003	1A		ALL
0130	20		G5		2-5	32-64-21	D46100J		3		TB0660Y	B003	1A		ALL
0131	20		G5		2-0	32-64-21	D46108J		22		TB0660Y	B023	1A		ALL
0132	20		G5		2-0	32-64-21	D46116J		4		TB0660Y	B023	1A		ALL
0133	20		G5		1-11	32-64-21	D46102J		16		TB0660Y	B023	1A		ALL
0134	20		PA		1-7	32-64-21	D46104J		32		D46102J		31		ALL
0135	20		PA		1-6	32-64-21	D46150J		24		D46102J		30		ALL
0136	20		PA		2-0	33-36-11	D46102J		32		TB0662Y	A003	1A		ALL
0137	20		PA		2-8	33-36-11	D46142J		A06		TB0662Y	A003	1A		ALL
0138	20		PA		2-4	33-36-11	D46100J		14		TB0662Y	A003	1A		ALL
0139	20		PA		2-4	33-36-12	D46100J		15		TB0662Y	B003	1A		ALL
0140	20		PA		2-0	33-36-12	D46102J		33		TB0662Y	B003	1A		ALL
0141	20		PA		2-8	33-36-12	D46142J		A07		TB0662Y	B003	1A		ALL
0142	20		G5		1-11	SPARE	D46110J		A02		D46102J		24		YC051-YD170
0142	20		G5		1-11	33-45-11	D46110J		A02		D46102J		24		YL951-YR328
0143	20		G5		1-5	SPARE	D46116J		14		D46102J		25		YC051-YD170
0143	20		G5		1-5	33-45-11	D46116J		14		D46102J		25		YL951-YR328
0144	16		CQ		1-7	SPARE	D46104J		23		D46102J		23		YC051-YD170
0144	16		CQ		1-7	33-45-11	D46104J		23		D46102J		23		YL951-YR328
0145	20		PA		2-3	34-41-11	D46100J		18		TB0662Y	A005	1A		YC051-YC052
0146	20		PA		2-4	34-41-11	D40107J		B01		TB0662Y	A005	1A		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W0060

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0066	286A0066				J46 INTEGRATION PANEL WIRING (continued)										
0147	20	PA			2-4	34-41-11	D40107J	B02			TB0662Y	A005	1A		YC051-YC052
0148	22	PA			1-10	34-41-11	D46122J	13			D40107J	B05			YC051-YC052
0149	22	PA			2-6	34-41-11	D40099J	A06			D40107J	B06			YC051-YC052
0150	22	PA			2-6	34-41-11	D40099J	A07			D40107J	B07			YC051-YC052
0151	22	PA			2-6	34-41-11	D40099J	A05			D40107J	B10			YC051-YC052
0152	22	PA			2-2	34-53-21	D46100J	4			D40103J	A01			ALL
0153	22	PA			2-3	34-53-31	D40103J	A06			TB0662Y	A007	1A		ALL
0154	22	PA			2-3	34-53-31	D40103J	A07			TB0662Y	A007	1A		ALL
0155	22	PA			2-3	34-53-31	D40103J	A08			TB0662Y	A007	1A		ALL
0156	22	PA			2-3	34-53-31	D46100J	5			TB0662Y	B007	1A		ALL
0157	22	PA			2-3	34-53-31	D40103J	A05			TB0662Y	B007	1A		ALL
0158	22	PA			2-3	34-53-31	D40103J	A04			TB0662Y	B007	1A		ALL
0160	24	PK			1-11	52-71-11	D46112J	7			D46122J	5			YC051-YD157
0161	24	PK			1-11	52-71-11	D46112J	8			D46122J	6			ALL
0162	24	PK			1-11	SPARE	D46112J	9			D46122J	3			YC051-YC052, YC060-YR328
0162	24	PK			2-4	SPARE	D46112J	9			TB0666Y	B001	1A		YC053-YC059
0163	24	PK			1-11	52-71-11	D46112J	10			D46122J	2			ALL
0164	24	PK			1-11	52-71-11	D46112J	11			D46122J	4			ALL
0165	24	PK			1-11	52-71-12	D46112J	12			D46122J	9			ALL
0166	24	PK			1-6	52-71-12	D46108J	23			D46122J	8			ALL
0167	24	PK			1-11	52-71-12	D46112J	13			D46122J	7			ALL
0168	24	G6			2-1	73-22-31	D46150J	9			D46118J	A04			ALL
0169	22	CQ			1-7	78-32-61	D46120J	B07			D46106J	15			ALL
0170	22	CQ			1-7	78-32-61	D46120J	A07			D46106J	16			ALL
0179	20	G5			2-1	73-22-11	D46150J	8			D46118J	B02			ALL
0180	22	PA			1-6	27-62-11	D46122J	29			D46116J	24			ALL
0181	22	PA			2-8	27-62-11	D46130J	A03			TB0664Y	B001	1A		ALL
0182	22	PA			2-2	27-62-11	D46106J	11			TB0664Y	B001	1A		ALL
0183	22	PA			2-2	27-62-11	D46122J	26			TB0664Y	B001	1A		ALL
0184	24	G6			2-1	76-21-21	D46150J	13			D46118J	A08			ALL
0185	24	PK			1-9	76-21-21	D46106J	12			D46100J	19			ALL
0186	24	PK			1-9	76-21-21	D46106J	13			D46100J	20			ALL
0187	24	B6			1-9	76-21-21	D46118J	B09			D46126J	5			ALL
0189	20	CQ			2-0	76-21-21	D46126J	7			TB0666Y	A001	1A		ALL
0190	20	CQ			2-2	76-21-21	D46106J	14			TB0666Y	A001	1A		ALL
0191	20	CQ			2-5	76-21-21	D46118J	A10			TB0666Y	A001	1A		ALL
0192	24	PK			1-9	36-11-11	D46114J	14			D46106J	17			ALL
0193	24	PK			2-2	36-11-11	D46114J	15			TB0662Y	A011	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0060

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0066	286A0066			J46 INTEGRATION PANEL WIRING (continued)											
0194	24	PK		2-2	36-11-11	D46106J		18			TB0662Y	A011	1A		ALL
0195	24	PK		2-2	36-11-11	D46114J		16			TB0662Y	A011	1A		ALL
0196	24	G6		2-6	36-11-11	D46112J		14			D46128J	A09			ALL
0197	24	G6		2-3	36-11-11	D46112J		15			TB0664Y	A003	1A		ALL
0198	24	G6		2-9	36-11-11	D46128J		A10			TB0664Y	A003	1A		ALL
0199	24	G6		2-3	36-11-11	D46112J		16			TB0664Y	A003	1A		ALL
0200	20	G5		2-1	74-11-11	D46150J		10			D46118J	A07			ALL
0201	22	G5		1-8	30-31-12	D46112J		6			D40097J	A04			ALL
0203	22	PA		1-9	32-64-21	D46106J		8			D46102J	14			ALL
0204	22	PA		1-9	32-64-21	D46106J		9			D46102J	15			ALL
0205	24	PK		2-3	34-53-21	D40103J		A02			TB0662Y	B005	1A		YC051-YC052
0206	24	PK		2-3	34-53-21	D40103J		A03			TB0662Y	B005	1A		YC051-YC052
0207	24	PK		2-4	34-53-21	D40107J		A07			TB0662Y	B005	1A		YC051-YC052
0208	20	CQ		2-0	76-21-21	D46126J		6			TB0666Y	A001	1A		ALL
0209	20	PA		2-1	27-62-11	D46100J		38			TB0664Y	A005	1A		ALL
0210	20	PA		2-1	27-62-11	D46100J		39			TB0664Y	B005	1A		ALL
0211	20	PA		1-6	52-71-13	D46116J		8			D46122J	18			ALL
0212	20	CQ		1-6	52-71-13	D46108J		26			D46116J	10			YC051-YL999, YR301-YR328
0212	20	CQ		1-6	SPARE	D46108J		26			D46116J	10			YN231-YN501
0213	20	CQ		1-6	52-71-13	D46108J		27			D46116J	9			ALL
0214	20	PA		2-0	52-71-14	D46120J		B09			D46122J	16			ALL
0215	20	PA		2-0	52-71-14	D46120J		B10			D46122J	17			ALL
0216	20	CQ		1-6	52-71-14	D46108J		28			D46122J	14			YC051-YL999, YR301-YR328
0216	20	CQ		1-6	SPARE	D46108J		28			D46122J	14			YN231-YN501
0217	20	CQ		1-6	52-71-14	D46108J		29			D46122J	15			ALL
0224	22	PA		1-10	34-41-11	D46106J		5			D46116J	31			YC053-YR328
0242	22	PA		2-4	52-71-11	TB0666Y		A003	1A		D46112J	7			YD158-YR328
0243	22	PA		2-3	52-71-11	TB0666Y		A003	1A		D46122J	5			YD158-YR328
0245	22	PA		2-3	23-32-14	TB0666Y		A003	1A		D46122J	10			YD158-YN260
0245	22	PA		2-3	44-21-22	TB0666Y		A003	1A		D46122J	10			YN501-YR328
0246	22	PA		1-6	23-32-14	D46122J		24			D46116J	7			YD158-YN260
0246	22	PA		1-6	44-21-22	D46122J		24			D46116J	7			YN501-YR328
0259	20	PA		2-6	28-23-11	D46130J		B01			D46120J	A08			YD158-YR328
0260	20	PA		2-6	28-23-11	D46130J		B02			D46120J	A09			YD158-YR328
0261	20	PA		2-6	28-23-11	D46130J		B03			D46120J	B08			YD158-YR328
0262	20	PA		1-7	44-21-10	D46104J		35			D46102J	36			YN501-YR328
0263	20	PA		1-7	44-21-10	D46104J		36			D46102J	37			YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0060

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0066	286A0066				J46 INTEGRATION PANEL WIRING (continued)										
0268	22		G5		1-11	21-27-21	D46122J		38		D46130J	A10			YL951-YR328
0269	22		G5		1-11	21-27-21	D46122J		39		D46130J	B10			YL951-YR328
0270	24		G6		2-3	21-43-21	D46108J		6		TB0666Y	B003	1A		YL951-YR328
0271	24		G6		2-10	21-43-21	D46128J		B04		TB0666Y	B003	1A		YL951-YR328
0272	24		G6		2-5	21-43-21	TB0666Y		B003	1A	D46120J	B02			YL951-YR328
0299	22		PA		2-2	27-62-21	D46102J		27		TB0664Y	B003	1A		YL953-YL999, YR301-YR328
0304	22		PA		2-8	27-62-11	D46128J		B08		TB0664Y	B005	1A		YL953-YL999, YR301-YR328
0305	22		PA		1-6	27-62-11	TB0664Y		B013	1A	TB0664Y	B003	1A		YL953-YL999, YR301-YR328
0306	22		PA		2-7	27-62-11	D46128J		B09		TB0664Y	B009	1A		YL953-YL999, YR301-YR328
0333	20		PA		2-6	27-62-11	TB0664Y		A013	1A	D46128J	B07			YL953-YL999, YR301-YR328
0334	20		PA		2-6	28-23-11	D46130J		B05		D46120J	B05			YL951-YR328
0336	22		CQ		2-6	31-53-11	TB0660Y		B001	1A	TB0664Y	A019	1A		YL951, YN231
0336	22		CQ		2-2	31-53-11	TB0662Y		A019	1A	TB0664Y	A019	1A		YL952-YL999, YN232-YR328
0337	22		CQ		1-11	31-53-11	TB0664Y		B019	1A	D46116J	41			YL951-YL952, YN231-YN232
0337	22		CQ		0-7	31-53-11	D46116J		40		D46116J	41			YL953-YL999, YN233-YR328
0338	22		CQ		1-11	31-53-11	SM00005			W	D46104J	38			YL951-YL952, YN231-YN232
0338	22		CQ		2-3	31-53-11	SM00005			W	TB0662Y	B021	1A		YL953-YL999, YN233-YR328
0339	22		CQ		0-8	31-53-11	TB0664Y		B019	1A	SM00005			W	YL951-YR328
0340	22		PA		2-3	21-33-11	D46104J		39		TB0664Z	A021	1A		YL951, YN231
0340	22		CQ		2-3	21-33-11	D46104J		39		TB0664Z	A021	1A		YL952-YL999, YN232-YR328
0341	22		PA		2-2	21-33-11	D46116J		11		TB0664Z	A021	1A		YL951, YN231
0341	22		CQ		2-2	21-33-11	D46116J		11		TB0664Z	A021	1A		YL952-YL999, YN232-YR328
0342	22		G5		2-4	46-11-51	D46144J		A07		D46110J	A07			YL951-YL954, YN231-YN235
0356	22		CQ		3-0	21-33-11	D46100J		34		D46126J	32			YC060-YC064
0356	22		CQ		1-11	21-33-11	D46142J		A09		D46126J	32			YL952-YL999, YN232-YR328

WIRE LIST
D280A108

91-21-11
Section W0060
Page 8
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0066	286A0066			J46 INTEGRATION PANEL WIRING (continued)											
0357	22		CQ		3-0	21-33-11	D46100J		35		TB0662Y	B019	1A		YC060-YC064
0357	22		CQ		2-4	21-33-11	D46142J		A10		TB0662Y	B019	1A		YL952-YL999, YN232-YR328
0358	22		CQ		3-0	21-33-11	D40097J		B09		TB0660Y	A003	1A		YC060-YC064
0358	22		CQ		2-6	21-33-11	D40097J		B09		TB0664Z	A021	1A		YL952-YL999, YN232-YR328
0359	22		CQ		1-7	31-53-11	D46116J		39		D46104J		38		YL953-YL999, YN233-YR328
0799	22		CQ		2-0	31-53-11	TB0662Y		A021	1A	D46116J		37		YL953-YL999, YN233-YR328
1001	20		X1	AA	2-4	73-22-11	D46118J		B01		D46144J		A06		ALL
1001Z				AA	0-0	73-22-11	D46118J		PERG	1F	D46144J		PERG	1F	ALL
1002	20		X1	AB	2-4	74-11-11	D46118J		A05		D46144J		A05		ALL
1002Z				AB	0-0	74-11-11	D46118J		PERG	1F	D46144J		PERG	1F	ALL
1003	20		X1	AC	1-8	74-11-11	D46132J		A05		D46136J		A07		ALL
1003Z				AC	0-0	74-11-11	D46132J		PERG	1F	D46136J		PERG	1F	ALL
1004	20		X1	AD	2-2	27-62-11	D46150J		25		TB0664Y		A005	1A	ALL
1004Z				AD	0-0	27-62-11	D46150J		26		TB0664Y				AA ALL
1005	20		X1	AE	2-2	27-62-11	D46150J		27		TB0664Y		A005	1A	ALL
1005Z				AE	0-0	27-62-11	D46150J		28		TB0664Y				AA ALL
1006	20		X1	AF	2-2	27-62-11	D46150J		11		TB0664Y		B005	1A	ALL
1006Z				AF	0-0	27-62-11	D46150J		12		TB0664Y		A007	1A	YC051-YL952, YN231-YN501
1006Z				AF	0-0	27-62-11	D46150J		12		SM00002			W	YL953-YL999, YR301-YR328
1007	20		X1	AG	2-1	27-62-11	D46150J		4		TB0664Y		B009	1A	YC051-YL952, YN231-YN501
1007	20		X1	AG	2-2	27-62-11	D46150J		4		TB0664Y		B007	1A	YL953-YL999, YR301-YR328
1007Z				AG	0-0	27-62-11	D46150J		5		TB0664Y		B007	1A	YC051-YL952, YN231-YN501
1007Z				AG	0-0	27-62-11	D46150J		5		SM00002			W	YL953-YL999, YR301-YR328
1008	20		X1	AH	2-2	27-62-11	D46150J		2		TB0664Y		B005	1A	ALL
1008Z				AH	0-0	27-62-11	D46150J		3		TB0664Y		A007	1A	YC051-YL952, YN231-YN501
1008Z				AH	0-0	27-62-11	D46150J		3		SM00002			W	YL953-YL999, YR301-YR328
1009	20		X1	AI	2-1	27-62-11	D46150J		6		TB0664Y		B009	1A	ALL

WIRE LIST

D280A108

91-21-11

Section W0060

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0066	286A0066			J46 INTEGRATION PANEL WIRING (continued)											
1009Z				AI	0-0	27-62-11	D46150J	7			TB0664Y	B007	1A		YC051-YL952, YN231-YN501
1009Z				AI	0-0	27-62-11	D46150J	7			SM00004		W		YL953-YL999, YR301-YR328
1010	20	X1	AJ		2-0	27-62-11	D46100J	36			TB0664Y	B009	1A		ALL
1010Z			AJ		0-0	27-62-11	D46100J	37			TB0664Y	B007	1A		YC051-YL952, YN231-YN501
1010Z			AJ		0-0	27-62-11	D46100J	37			SM00004		W		YL953-YL999, YR301-YR328
1011	20	X1	AK		1-5	27-62-11	TB0664Y	A007	1A		TB0664Y	B009	1A		YL953-YL999, YR301-YR328
1011Z			AK		0-0	27-62-11	SM00002		W		SM00004		W		YL953-YL999, YR301-YR328
2001B	22	PB	GA		2-2	30-21-21	D46114J	9			D46144J	A03			ALL
2001R	22	PB	GA		0-0	30-21-21	D46114J	8			D46144J	A02			ALL
2002B	24	Y2	GB		2-6	31-62-23	D40099J	A02			D40107J	A02			YC051-YC052
2002R	24	Y2	GB		0-0	31-62-23	D40099J	A01			D40107J	A01			YC051-YC052
2002Z			GB		0-0	31-62-23	D40099J	PERG	1F		D40107J	PERG	1F		YC051-YC052
2003B	24	PL	GC		1-11	32-31-12	D46102J	5			D46136J	A02			ALL
2003R	24	PL	GC		0-0	32-31-12	D46102J	6			D46136J	A01			ALL
2004B	22	GL	GD		1-11	32-64-12	D46102J	12			D46136J	A04			ALL
2004R	22	GL	GD		0-0	32-64-12	D46102J	13			D46136J	A03			ALL
2005B	22	GL	GE		1-11	32-64-12	D46102J	10			D46136J	A06			ALL
2005R	22	GL	GE		0-0	32-64-12	D46102J	11			D46136J	A05			ALL
2009B	24	Y2	GI		2-7	34-21-23	D40107J	A04			D40097J	A06			YC051-YC052
2009R	24	Y2	GI		0-0	34-21-23	D40107J	A03			D40097J	A05			YC051-YC052
2009Z			GI		0-0	34-21-23	D40107J	PERG	1F		D40097J	PERG	1F		YC051-YC052
2010B	24	7K	GJ		2-6	34-41-11	D40099J	A04			D40107J	B04			YC051-YC052
2010W	24	7K	GJ		0-0	34-41-11	D40099J	A03			D40107J	B03			YC051-YC052
2010Z			GJ		0-0	34-41-11	D40099J	PERG	1F		D40107J	PERG	1F		YC051-YC052
2011B	24	Y2	GK		2-6	34-41-11	D40099J	A09			D40107J	B09			YC051-YC052
2011R	24	Y2	GK		0-0	34-41-11	D40099J	A08			D40107J	B08			YC051-YC052
2011Z			GK		0-0	34-41-11	D40099J	PERG	1F		D40107J	PERG	1F		YC051-YC052
2012B	24	Y2	GL		2-4	73-21-11	D46118J	A02			D46146J	A02			ALL
2012R	24	Y2	GL		0-0	73-21-11	D46118J	A01			D46146J	A01			ALL
2012Z			GL		0-0	73-21-11	D46118J	PERG	1F		D46146J	PERG	1F		ALL
2015B	24	Y2	GP		2-7	34-21-24	D40107J	A06			D40097J	A08			YC051-YC052
2015R	24	Y2	GP		0-0	34-21-24	D40107J	A05			D40097J	A07			YC051-YC052
2015Z			GP		0-0	34-21-24	D40107J	PERG	1F		D40097J	PERG	1F		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W0060

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity

W0066 286A0066 J46 INTEGRATION PANEL WIRING (continued)

2022B	22	PB	GW	1-9	24-22-21	D46106J		1			D46122J	11			ALL
2022R	22	PB	GW	0-0	24-22-21	D46106J		2			D46122J	12			ALL

For training purposes only!

WIRE LIST

D280A108

91-21-11

Section W0060

Page 11 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0071	286A0071				P61 - FIRST OBSERVERS OXY MASK MIC										
2001B	26	6Z	EB		1-3	23-51-31	D04005J	= 1	VS		D06053	1	\$		YC051-YD158, YL951-YL952, YN231-YN234
2001B	26	6Z	EB		1-4	23-51-31	D04005J	= 1	VS		D06053	1	\$		YD160-YD170, YL953-YL999, YN235-YR328
2001R	26	6Z	EB		0-0	23-51-31	D04003P	= 1	VG		D06053	3	\$		ALL
W0072	286A0072				J20 JUNCTION BOX-PLATE B (CONTAINS ENGINE 2 WIRING)										
0006	22	GA			1-7	26-16-21	D40638J		13		D11026	D2			YC053, YC055, YC060-YC064
0006	22	PA			1-4	26-16-21	D40638J		13		D11026	D2			YC067-YR328
0007	22	GA			1-7	26-16-21	D40640J		12		D11026	D3			YC053, YC055, YC060-YC064
0007	22	PA			1-4	26-16-21	D40640J		12		D11026	D3			YC067-YD157
0007	22	PA			1-6	26-16-21	D40640J		12		D11026	D3			YD158-YR328
0051	24	B6			1-1	32-31-12	D11024		X1		TB0020Y	A011	1A		YC051-YD157
0051	24	B6			1-6	32-31-12	D11024		X1		TB0020Y	A011	1A		YD158-YR328
0052	24	B6			1-9	32-31-12	D11024		X2		D40632J	21			YC051-YD157
0052	24	B6			1-10	32-31-12	D11024		X2		D40632J	21			YD158-YR328
0053	24	G6			1-5	21-51-11	D40640J		10		D11024	A1			YC051-YD157
0053	24	G6			1-7	21-51-11	D40640J		10		D11024	A1			YD158-YR328
0054	24	G6			1-5	21-51-11	D11024		A2		D40640J	11			YC051-YD157
0054	24	G6			1-7	21-51-11	D11024		A2		D40640J	11			YD158-YR328
0055	18	PA			1-8	29-25-11	D11024		B1		D40640J	7			ALL
0056	22	PA			1-8	29-25-11	D11024		B2		D40640J	5			ALL
0057	18	PA			1-8	29-25-11	D11024		B3		D40640J	6			ALL
0061	24	B6			1-2	32-31-12	D11026		X1		TB0020Y	A011	1A		YC051-YD157
0061	24	B6			1-5	32-31-12	D11026		X1		TB0020Y	A011	1A		YD158-YR328
0062	24	PK			1-7	32-31-12	D40632J		2		D11026	X2			YC051-YD157
0062	24	PK			1-9	32-31-12	D40632J		2		D11026	X2			YD158-YR328
0063	24	PK			1-7	32-51-11	D11026		A1		D40632J	7			YC051-YD157
0063	24	PK			1-9	32-51-11	D11026		A1		D40632J	7			YD158-YR328
0064	24	PK			1-4	32-51-11	D40638J		1		D11026	A2			ALL
0065	24	PK			1-7	32-51-11	D11026		A3		D40632J	6			YC051-YD157
0065	24	PK			1-9	32-51-11	D11026		A3		D40632J	6			YD158-YR328
0071	24	PK			1-4	32-31-12	D11016		X1		TB0020Y	B011	1A		YC051-YD157
0071	24	PK			1-5	32-31-12	D11016		X1		TB0020Y	B011	1A		YD158-YR328
0072	24	PK			1-7	32-31-12	D40632J		3		D11016	X2			YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0070

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0072	286A0072			J20 JUNCTION BOX-PLATE B (CONTAINS ENGINE 2 WIRING) (continued)											
0072	24		PK		1-8	32-31-12	D40632J		3		D11016		X2		YD158-YR328
0076	22		PA		1-2	27-62-11	D11016		B1		D40634J		8		YC051-YD157
0076	22		PA		1-3	27-62-11	D11016		B1		D40634J		8		YD158-YR328
0077	22		PA		1-5	27-62-11	D11016		B2		TB0020Y	A013	1A		ALL
0078	22		PA		1-2	27-62-11	D11016		B3		D40634J		7		YC051-YD157
0078	22		PA		1-3	27-62-11	D11016		B3		D40634J		7		YD158-YR328
0081	24		PK		1-6	32-31-12	D11014		X1		TB0020Y	B011	1A		YC051-YD157
0081	24		PK		1-7	32-31-12	D11014		X1		TB0020Y	B011	1A		YD158-YR328
0082	24		PK		1-9	32-31-12	D40632J		4		D11014		X2		YC051-YD157
0082	24		PK		1-4	32-31-12	D40632J		4		D11014		X2		YD158-YR328
0091	24		PK		1-5	32-31-12	D11010		X1		TB0020Y	B011	1A		YC051-YD157
0091	24		PK		1-6	32-31-12	D11010		X1		TB0020Y	B011	1A		YD158-YR328
0092	24		PK		1-8	32-31-12	D11010		X2		D40632J		5		YC051-YD157
0092	24		PK		1-10	32-31-12	D11010		X2		D40632J		5		YD158-YR328
0093	20		PA		1-5	27-23-11	D11010		A1		D40638J		7		ALL
0094	20		PA		1-5	27-23-11	D11010		A2		D40638J		8		ALL
0095	18		PA		2-0	38-31-31	D11010		B1		D40636J		7		YL951-YL999, YR301-YR328
0095	18		PA		1-8	38-31-31	D11010		B1		D40636J		7		YN231-YN501
0096	18		PA		2-0	38-31-31	D11010		B2		D40636J		5		YL951-YL999, YR301-YR328
0096	18		PA		1-8	38-31-31	D11010		B2		D40636J		5		YN231-YN501
0097	18		PA		2-0	38-31-31	D11010		B3		D40636J		6		YL951-YL999, YR301-YR328
0097	18		PA		1-8	38-31-31	D11010		B3		D40636J		6		YN231-YN501
0098	22		PA		1-1	27-62-11	D11010		C1		D40634J		10		ALL
0099	22		PA		1-6	27-62-11	D11010		C2		TB0020Y	A013	1A		ALL
0100	22		PA		1-1	27-62-11	D11010		C3		D40634J		9		ALL
0101	24		PK		1-6	76-21-21	D10924		X1		TB0020Y	B009	1A		YC051-YD157
0101	24		PK		1-5	76-21-21	D10924		X1		TB0020Y	B009	1A		YD158-YR328
0102	24		PK		1-6	76-21-21	D40634J		6		D10924		X2		YC051-YD157
0102	24		PK		1-8	76-21-21	D40634J		6		D10924		X2		YD158-YR328
0103	24		PK		1-6	76-21-21	D10924		Y1		TB0020Y	B009	1A		YC051-YD157
0103	24		PK		1-5	76-21-21	D10924		Y1		TB0020Y	B009	1A		YD158-YR328
0104	24		PK		1-6	76-21-21	D40634J		5		D10924		Y2		YC051-YD157
0104	24		PK		1-8	76-21-21	D40634J		5		D10924		Y2		YD158-YR328
0105	18		CQ		1-6	24-11-21	D40638J		4		D10924		C2		YC051-YD157
0105	18		CQ		1-9	24-11-21	D40638J		4		D10924		C2		YD158-YR328
0106	18		CQ		1-6	24-11-21	D10924		C3		D40638J		5		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0070

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0072	286A0072			J20 JUNCTION BOX-PLATE B (CONTAINS ENGINE 2 WIRING) (continued)											
0106	18		CQ		1-9	24-11-21	D10924		C3		D40638J		5		YD158-YR328
0111	24		G6		1-8	21-27-31	D11868		X1		D40632J		8		YC051-YD157
0111	24		G6		1-7	21-27-31	D11868		X1		D40632J		8		YD158-YR328
0112	20		G5		1-7	21-27-31	D11868		X2		GD00528	DC..	1A		YC051-YD157
0112	20		G5		1-6	21-27-31	D11868		X2		GD00528	DC..	1A		YD158-YR328
0113	24		B6		1-5	21-27-31	D11868		A2		TB0020Y	B001	1A		YC051-YD157
0113	24		B6		1-6	21-27-31	D11868		A2		TB0020Y	B001	1A		YD158-YR328
0114	22		G5		1-5	21-27-31	D11868		A3		D40638J		9		YC051-YD157
0114	22		G5		1-7	21-27-31	D11868		A3		D40638J		9		YD158-YR328
0116	22		PA		1-5	21-27-31	D11868		B2		D40634J		12		YC051-YD157
0116	22		PA		1-6	21-27-31	D11868		B2		D40634J		12		YD158-YR328
0117	22		PA		1-5	21-27-31	D11868		B3		D40634J		13		YC051-YD157
0117	22		PA		1-6	21-27-31	D11868		B3		D40634J		13		YD158-YR328
0118	22		G5		1-5	21-27-31	D11868		C1		D40634J		19		YC051-YD157
0118	22		G5		1-6	21-27-31	D11868		C1		D40634J		19		YD158-YR328
0119	22		CQ		1-5	21-27-31	D11868		C2		D40634J		17		YC051-YD157
0119	22		CQ		1-6	21-27-31	D11868		C2		D40634J		17		YD158-YR328
0120	24		G6		1-5	21-27-31	D11868		D2		TB0020Y	A005	1A		YC051-YD157
0120	24		G6		1-6	21-27-31	D11868		D2		TB0020Y	A005	1A		YD158-YR328
0121	22		G5		1-8	21-27-31	D11868		D3		D40636J		3		YC051-YD157
0121	22		G5		1-5	21-27-31	D11868		D3		D40636J		3		YD158-YR328
0132	24		G6		1-10	21-27-31	D12250		2		TB0020Y	A005	1A		YC051-YD157
0132	24		G6		1-8	21-27-31	D12250		2		TB0020Y	A005	1A		YD158-YR328
0133	22		G5		1-10	21-27-31	D12250		3		TB0020Y	A001	1A		YC051-YD157
0133	22		G5		1-8	21-27-31	D12250		3		TB0020Y	A001	1A		YD158-YR328
0134	20		G5		1-0	21-27-31	D12250		4		GD00528	DC..	1A		YC051-YD157
0134	20		G5		1-6	21-27-31	D12250		4		GD00528	DC..	1A		YD158-YR328
0137	22		G5		1-7	21-27-31	D12250		7		D40636J		1		YC051-YD157
0137	22		G5		1-5	21-27-31	D12250		7		D40636J		1		YD158-YR328
0151	22		PA		1-7	27-62-11	D10569		X1		TB0020Z	A017	1A		YC051-YD157
0151	22		PA		1-3	27-62-11	D10569		X1		TB0020Z	A017	1A		YD158-YR328
0152	22		PA		1-6	27-62-11	D10569		X2		TB0020Y	B013	1A		YC051-YD157
0152	22		PA		1-2	27-62-11	D10569		X2		TB0020Y	B013	1A		YD158-YR328
0153	22		PA		1-7	27-62-11	D10569		A1		GD00528	DC..	1A		YC051-YD157
0153	22		PA		1-5	27-62-11	D10569		A1		GD00528	DC..	1A		YD158-YR328
0154	22		PA		1-7	27-62-11	D40632J		15		D10569		A2		YC051-YD157
0154	22		PA		1-6	27-62-11	D40632J		15		D10569		A2		YD158-YR328
0157	20		PA		1-6	47-30-11	D11026		C1		D40858J		20		YD160-YR328
0161	22		PA		1-9	27-62-11	D40636J		9		D10573		X1		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0070

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0072		286A0072				J20 JUNCTION BOX-PLATE B (CONTAINS ENGINE 2 WIRING) (continued)									
	0161	22	PA		1-4	27-62-11	D40636J		9		D10573		X1		YD158-YR328
	0162	22	PA		1-9	27-62-11	D40636J		8		D10573		X2		YC051-YD157
	0162	22	PA		1-4	27-62-11	D40636J		8		D10573		X2		YD158-YR328
	0163	22	PA		1-6	27-62-11	D10573		A1		TB0020Y	B013	1A		YC051-YD157
	0163	22	PA		1-3	27-62-11	D10573		A1		TB0020Y	B013	1A		YD158-YR328
	0164	22	PA		1-8	27-62-11	D10573		A2		GD00528	DC..	1A		YC051-YD157
	0164	22	PA		1-5	27-62-11	D10573		A2		GD00528	DC..	1A		YD158-YR328
	0167	22	PA		1-8	27-62-11	D40632J		14		D10573		B2		YC051-YD157
	0167	22	PA		1-6	27-62-11	D40632J		14		D10573		B2		YD158-YR328
	0168	22	PA		1-5	27-62-11	D10573		B3		TB0020Y	B007	1A		ALL
	0169	22	PA		1-6	27-62-11	D10573		C1		TB0020Y	A015	1A		YC051-YD157
	0169	22	PA		1-3	27-62-11	D10573		C1		TB0020Y	A015	1A		YD158-YR328
	0170	22	PA		1-8	27-62-11	D40632J		13		D10573		C2		YC051-YD157
	0170	22	PA		1-6	27-62-11	D40632J		13		D10573		C2		YD158-YR328
	0171	22	PA		1-8	27-62-11	D10573		C3		GD00528	DC..	1A		YC051-YD157
	0171	22	PA		1-5	27-62-11	D10573		C3		GD00528	DC..	1A		YD158-YR328
	0172	20	PA		1-5	78-34-21	D10573		D1		D40634J		25		ALL
	0173	20	PA		1-8	78-34-21	D10573		D2		GD00528	DC..	1A		YC051-YD157
	0173	20	PA		1-5	78-34-21	D10573		D2		GD00528	DC..	1A		YD158-YR328
	0176	22	PA		1-11	27-62-11	D10575		6		TB0020Z	A017	1A		YC051-YD157
	0176	22	PA		1-4	27-62-11	D10575		6		TB0020Z	A017	1A		YD158-YR328
	0177	22	PA		1-5	27-62-11	D10575		12		GD00528	DC..	1A		YC051-YD157
	0177	22	PA		1-6	27-62-11	D10575		12		GD00528	DC..	1A		YD158-YR328
	0178	22	PA		1-8	27-62-11	D10575		13		TB0020Y	A007	1A		ALL
	0181	22	PA		1-7	27-62-11	D10577		X1		TB0020Y	A007	1A		ALL
	0182	22	PA		1-10	27-62-11	D10577		X2		D10581		5		YC051-YD157
	0182	22	PA		1-6	27-62-11	D10577		X2		D10581		5		YD158-YR328
	0183	22	PA		1-9	27-62-11	D10575		1		D10577		Y1		YC051-YD157
	0183	22	PA		1-4	27-62-11	D10575		1		D10577		Y1		YD158-YR328
	0184	22	PA		1-9	27-62-11	D10577		Y2		GD00528	DC..	1A		YC051-YD157
	0184	22	PA		1-7	27-62-11	D10577		Y2		GD00528	DC..	1A		YD158-YR328
	0185	22	PA		1-9	27-62-11	D10577		A1		GD00528	DC..	1A		YC051-YD157
	0185	22	PA		1-7	27-62-11	D10577		A1		GD00528	DC..	1A		YD158-YR328
	0186	22	PA		1-7	27-62-11	D10577		A2		TB0020Y	B007	1A		ALL
	0187	22	PA		1-3	27-62-11	D10579		6		M02033		B C		YC051-YD157
	0187	22	PA		1-1	27-62-11	D10579		6		M02033		B C		YD158-YR328
	0189	22	PA		1-5	27-62-11	D10579		12		GD00528	DC..	1A		YC051-YD157
	0189	22	PA		1-6	27-62-11	D10579		12		GD00528	DC..	1A		YD158-YR328
	0190	22	PA		1-5	27-62-11	D10579		14		GD00528	DC..	1A		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0070

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0072	286A0072			J20 JUNCTION BOX-PLATE B (CONTAINS ENGINE 2 WIRING) (continued)											
0190	22		PA		1-6	27-62-11	D10579			14	GD00528	DC..	1A		YD158-YR328
0191	22		PA		1-11	27-62-11	D10581			4	TB0020Y	A015	1A		YC051-YD157
0191	22		PA		1-6	27-62-11	D10581			4	TB0020Y	A015	1A		YD158-YR328
0192	22		PA		2-0	27-62-11	D10581			6	TB0020Z	A017	1A		YC051-YD157
0192	22		PA		1-5	27-62-11	D10581			6	TB0020Z	A017	1A		YD158-YR328
0193	22		PA		1-1	27-62-11	D10579			7	D10581				ALL
0194	20		PA		1-6	47-30-11	D11026		C2		D40858J		19		YD160-YR328
0195	22		PA		1-8	27-62-11	M02033		A	C	TB0020Z	A017	1A		YC051-YD157
0195	22		PA		1-1	27-62-11	M02033		A	C	TB0020Z	A017	1A		YD158-YR328
0201	22		GA		1-9	23-31-06	D02375			3	D40634J		31		YC051-YC065
0201	22		PA		1-9	23-31-06	D02375			3	D40634J		31		YC067-YD153
0201	22		PA		2-0	23-31-06	D02375			3	TB0020Y	A023	1A		YD154-YD157
0201	22		PA		1-2	23-31-06	D02375			3	TB0020Y	A023	1A		YD158-YN260
0201	22		PA		1-2	44-21-22	D02375			3	TB0020Y	A023	1A		YN501-YR328
0202	22		GA		1-9	23-31-06	D02375			7	D40634J		30		YC051-YC065
0202	22		PA		1-9	23-31-06	D02375			7	D40634J		30		YC067-YD153
0202	22		PA		2-0	23-31-06	D02375			7	TB0020Y	B023	1A		YD154-YD157
0202	22		PA		1-2	23-31-06	D02375			7	TB0020Y	B023	1A		YD158-YN260
0202	20		PA		1-2	44-21-22	D02375			7	TB0020Y	B023	1A		YN501-YR328
0203	22		PA		1-10	23-31-06	D40634J			31	TB0020Y	A023	1A		YD154-YD157
0203	22		PA		1-9	23-31-06	D40634J			31	TB0020Y	A023	1A		YD158-YN260
0203	22		PA		1-9	44-21-22	D40634J			31	TB0020Y	A023	1A		YN501-YR328
0208	22		PA		1-10	23-31-06	D40634J			30	TB0020Y	B023	1A		YD154-YD157
0208	22		PA		1-9	23-31-06	D40634J			30	TB0020Y	B023	1A		YD158-YN260
0208	20		PA		1-9	44-21-22	D40634J			30	TB0020Y	B023	1A		YN501-YR328
0224	20		PA		1-9	27-62-11	D11010			D2	GD00528	DC..	1A		YL953-YL999, YR301-YR328
0225	22		PA		1-3	27-62-11	D11010			D1	SM00014		W		YL953-YL999, YR301-YR328
0226	22		PA		1-6	27-62-11	D10569			C2	SM00014		W		YL953-YL999, YR301-YR328
0227	22		PA		1-6	27-62-11	D40638J			10	D10569		C1		YL953-YL999, YR301-YR328
0228	22		PA		0-7	27-62-11	D40638J			11	SM00014		W		YL953-YL999, YR301-YR328
0230	22		PA		1-7	31-32-15	D12466			3	D40642J		1		YC051-YD157
0230	22		PA		1-4	31-32-15	D12466			3	D40642J		1		YD158-YR328
0231	20		CQ		1-7	49-62-11	D12466			7	D40642J		11		YC051-YD157
0231	20		CQ		1-4	49-62-11	D12466			7	D40642J		11		YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0070

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0072		286A0072				J20 JUNCTION BOX-PLATE B (CONTAINS ENGINE 2 WIRING) (continued)									
	0282	22	PA		1-1	23-42-11	D40858J		29		D12759		6		YL951-YR328
	0283	22	PA		1-1	23-42-11	D40858J		30		D12759		1		YL951-YR328
	0284	20	PA		1-4	23-42-11	D12759		3		GD00528	DC..	1A		YL951-YR328
	0285	22	PA		1-1	23-42-11	D40858J		31		D12759		7		YL951-YR328
	0288	22	PA		1-1	23-42-11	D40858J		28		D12759		2		YL951-YR328
	0289	20	PA		1-4	23-42-11	D12759		5		GD00528	DC..	1A		YL951-YR328
	0504	22	PA		1-7	27-62-11	D40634J		11		TB0020Y	A013	1A		YC051-YD157
	0504	22	PA		1-8	27-62-11	D40634J		11		TB0020Y	A013	1A		YD158-YR328
	0505	24	B6		1-6	32-31-12	D40638J		3		TB0020Y	A011	1A		YC051-YD157
	0505	24	B6		1-9	32-31-12	D40638J		3		TB0020Y	A011	1A		YD158-YR328
	0506	24	B6		1-10	32-31-11	D40632J		20		TB0020Y	A011	1A		YC051-YD157
	0506	24	B6		1-9	32-31-11	D40632J		20		TB0020Y	A011	1A		YD158-YR328
	0507	24	PK		1-10	32-31-12	D40632J		1		TB0020Y	B011	1A		YC051-YD157
	0507	24	PK		1-9	32-31-12	D40632J		1		TB0020Y	B011	1A		YD158-YR328
	0510	24	PK		1-6	76-21-21	D40634J		4		TB0020Y	B009	1A		YC051-YD157
	0510	24	PK		1-8	76-21-21	D40634J		4		TB0020Y	B009	1A		YD158-YR328
	0511	22	CQ		1-6	21-27-31	D40638J		6		TB0020Y	B001	1A		YC051-YD157
	0511	22	CQ		1-7	21-27-31	D40638J		6		TB0020Y	B001	1A		YD158-YR328
	0512	24	G6		0-7	21-27-31	TB0020Y	A003	1A		TB0020Y	A001	1A		ALL
	0514	22	G5		1-10	21-27-31	D40636J		2		TB0020Y	B005	1A		ALL
	0515	24	G6		1-0	21-27-31	TB0020Y	B003	1A		TB0020Y	B005	1A		ALL
	0519	22	PA		1-11	27-62-11	D40632J		11		TB0020Y	A015	1A		YC051-YD157
	0519	22	PA		1-9	27-62-11	D40632J		11		TB0020Y	A015	1A		YD158-YR328
	0520	22	PA		1-11	27-62-11	D40632J		12		TB0020Y	B013	1A		YC051-YD157
	0520	22	PA		1-9	27-62-11	D40632J		12		TB0020Y	B013	1A		YD158-YR328
	0521	22	PA		1-6	27-62-11	D40634J		26		TB0020Y	A007	1A		ALL
	0522	22	PA		1-8	27-62-11	D40634J		27		TB0020Z	A017	1A		YC051-YD157
	0522	22	PA		1-9	27-62-11	D40634J		27		TB0020Z	A017	1A		YD158-YR328
	0523	22	PA		1-6	27-62-11	D40634J		28		TB0020Y	B007	1A		ALL
	0601	20	PA		1-5	28-23-11	D40858J		1		D13796		X1		YD158
	0601	20	PA		0-7	28-23-11	D40858J		1		SM00603		W		YD160-YR328
	0602	20	PA		1-5	28-23-11	D40858J		2		D13796		A2		YD158-YR328
	0603	20	PA		0-7	28-23-11	D40858J		3		SM00601		W		YD158-YR328
	0604	20	PA		1-5	28-23-11	D13796		X2		SM00602		W		YD158-YR328
	0605	20	PA		1-5	28-23-11	D13796		A1		D13794		X1		YD158-YR328
	0606	20	PA		0-7	28-23-11	D40858J		6		SM00601		W		YD158-YR328
	0607	20	PA		1-1	28-23-11	D13794		X2		SM00601		W		YD158-YR328
	0608	20	PA		0-7	28-23-11	D40858J		4		SM00602		W		YD158-YR328
	0609	20	PA		1-1	28-23-11	D40858J		5		D13794		A3		YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0070

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0072	286A0072				J20 JUNCTION BOX-PLATE B (CONTAINS ENGINE 2 WIRING) (continued)											
0610	20		PA		1-1	28-23-11		D13794		A2		SM00602		W		YD158-YR328
0611	20		PA		1-5	28-23-11		D13796		X1		SM00603		W		YD160-YR328
0612	20		PA		1-1	28-23-11		D40858J		7		D13794		B2		YD160-YR328
0613	20		PA		1-1	28-23-11		D40858J		8		D13794		B3		YD160-YR328
0614	20		PA		0-7	28-23-11		D40858J		9		SM00603		W		YD160-YR328
1001	20		X1	AA	1-5	27-62-11		D40634J		22		D10569		B1		ALL
1001Z				AA	0-0	27-62-11		D40634J		23		D10569			AB	ALL
1002	20		X1	AB	1-5	27-62-11		D10569		B2		D40634J		21		ALL
1002Z				AB	0-0	27-62-11		D10569			AB	D40634J		20		ALL
2001B	24		Y2	GA	1-6	73-21-11		D10924		A2		D40634J		1		YC051-YD157
2001B	24		Y2	GA	1-8	73-21-11		D10924		A2		D40634J		1		YD158-YR328
2001R	24		Y2	GA	0-0	73-21-11		D10924		A1		D40634J		2		ALL
2001Z				GA	0-0	73-21-11		GB00020		ST..	1A	D40634J		3		ALL
2002B	24		PL	GB	1-9	23-31-06		D02375		4		D40634J		29		YC051-YD157
2002B	24		PL	GB	1-7	23-31-06		D02375		4		D40634J		29		YD158-YN260
2002B	24		PL	GB	1-7	44-21-22		D02375		4		D40634J		29		YN501-YR313
2002B	24		Y2	GB	1-7	44-21-22		D02375		4		D40634J		29		YR314-YR328
2002R	24		PL	GB	0-0	23-31-06		D02375		8		D40634J		24		YC051-YN260
2002R	24		PL	GB	0-0	44-21-22		D02375		8		D40634J		24		YN501-YR313
2002R	24		Y2	GB	0-0	44-21-22		D02375		8		D40634J		24		YR314-YR328
2002Z				GB	0-0	44-21-22		D02375		DED		D40634J		DED		YR314-YR328
2003B	24		PL	GC	1-9	23-31-06		D02375		2		D40634J		18		YC051-YD157
2003B	24		PL	GC	1-7	23-31-06		D02375		2		D40634J		18		YD158-YN260
2003B	24		PL	GC	1-7	44-21-22		D02375		2		D40634J		18		YN501-YR313
2003B	24		Y2	GC	1-7	44-21-22		D02375		2		D40634J		18		YR314-YR328
2003R	24		PL	GC	0-0	23-31-06		D02375		6		D40634J		16		YC051-YN260
2003R	24		PL	GC	0-0	44-21-22		D02375		6		D40634J		16		YN501-YR313
2003R	24		Y2	GC	0-0	44-21-22		D02375		6		D40634J		16		YR314-YR328
2003Z				GC	0-0	44-21-22		D02375		DED		D40634J		DED		YR314-YR328
2004B	24		PL	GD	1-9	23-31-06		D02375		5		D40634J		15		YC051-YD157
2004B	24		PL	GD	1-7	23-31-06		D02375		5		D40634J		15		YD158-YN260
2004B	24		PL	GD	1-7	44-21-22		D02375		5		D40634J		15		YN501-YR313
2004B	24		Y2	GD	1-7	44-21-22		D02375		5		D40634J		15		YR314-YR328
2004R	24		PL	GD	0-0	23-31-06		D02375		1		D40634J		14		YC051-YN260
2004R	24		PL	GD	0-0	44-21-22		D02375		1		D40634J		14		YN501-YR313
2004R	24		Y2	GD	0-0	44-21-22		D02375		1		D40634J		14		YR314-YR328
2004Z				GD	0-0	44-21-22		D02375		DED		D40634J		DED		YR314-YR328
2011B	24		Y2	GK	1-7	31-32-15		D12466		1		D40642J		3		YC051-YD157
2011B	24		Y2	GK	1-4	31-32-15		D12466		1		D40642J		3		YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0070

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY	Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice
W0072	286A0072	J20 JUNCTION BOX-PLATE B (CONTAINS ENGINE 2 WIRING) (continued)			
2011R	24	Y2	GK	0-0 31-32-15 D12466	5 D40642J 2 ALL
2011Z			GK	0-0 31-32-15 GB00020	ST.. 1A D40642J 4 ALL
2012B	24	Y2	GL	1-7 73-24-12 D12466	6 D40642J 6 YC051-YD157
2012B	24	Y2	GL	1-4 73-24-12 D12466	6 D40642J 6 YD158-YR328
2012R	24	Y2	GL	0-0 73-24-12 D12466	2 D40642J 5 ALL
2012Z			GL	0-0 73-24-12 GB00020	ST.. 1A D40642J 7 ALL
2013B	24	Y2	GM	1-7 73-24-12 D12466	8 D40642J 9 YC051-YD157
2013B	24	Y2	GM	1-4 73-24-12 D12466	8 D40642J 9 YD158-YR328
2013R	24	Y2	GM	0-0 73-24-12 D12466	4 D40642J 8 ALL
2013Z			GM	0-0 73-24-12 GB00020	ST.. 1A D40642J 10 ALL
W0074	286A0074	J20 JUNCTION BOX-PLATE A			
0006	22	PA		2-0 26-16-21 TB0028Y	B001 1A TB0028Y B003 1A YC053, YC055
0006	22	PA		2-0 26-16-21 TB0030Y	B001 1A TB0030Y B003 1A YC060-YC064
0006	22	PA		0-7 26-16-21 TB0028Y	B001 1A TB0028Y B003 1A YC067-YR328
0007	22	PA		2-0 26-16-21 D40884J	15 TB0028Y B003 1A YC053, YC055
0007	22	PA		1-9 26-16-21 D40884J	15 TB0030Y B003 1A YC060-YC064
0007	22	PA		1-9 26-16-21 D40884J	15 TB0028Y B003 1A YC067-YR328
0176	22	PA		1-2 30-31-12 D40884J	4 D13308 A3 YC060-YC064
0177	22	PA		1-2 30-31-12 D40884J	5 D13308 A1 YC060-YC064
0178	22	PA		1-2 30-31-12 D40884J	7 D13308 B3 YC060-YC064
0179	22	PA		1-2 30-31-12 D40884J	8 D13308 B1 YC060-YC064
0180	22	PA		1-2 30-31-12 D40884J	6 D13308 B2 YC060-YC064
0181	24	PK		1-2 32-31-12 D40884J	10 D13308 X1 YC060-YC064
0182	24	PK		1-2 32-31-12 D40884J	11 D13308 X2 YC060-YC064
0183	24	PK		2-0 21-31-22 D40878J	1 D13688 C2 YC053, YC055
0183	24	GK		2-0 21-31-22 D40878J	1 D13688 C2 YC060-YC064
0183	24	PK		1-5 21-31-22 D40878J	1 D13688 C2 YC067-YR328
0184	24	PK		2-0 21-31-22 D40878J	2 D13688 B2 YC053, YC055
0184	24	GK		2-0 21-31-22 D40878J	2 D13688 B2 YC060-YC064
0184	24	PK		1-5 21-31-22 D40878J	2 D13688 B2 YC067-YR328
0185	20	PA		2-0 21-31-22 D13688	A2 TB0028Y A001 1A YC053, YC055
0185	20	GA		1-8 21-31-22 D13688	A2 TB0030Y A001 1A YC060-YC064
0185	20	PA		1-8 21-31-22 D13688	A2 TB0028Y A001 1A YC067-YR328
0186	20	PA		2-0 21-31-22 D13688	X2 TB0028Y A001 1A YC053, YC055
0186	20	GA		1-8 21-31-22 D13688	X2 TB0030Y A001 1A YC060-YC064
0186	20	PA		1-8 21-31-22 D13688	X2 TB0028Y A001 1A YC067-YR328
0187	22	PA		2-0 21-31-22 D13688	C3 GD03704 DC.. 1A YC053, YC055
0187	22	GA		2-0 21-31-22 D13688	C3 GD03704 DC.. 1A YC060-YC064

WIRE LIST

D280A108

91-21-11

Section W0070

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0074	286A0074				J20 JUNCTION BOX-PLATE A (continued)										
0187	22		PA		1-8	21-31-22	D13688		C3		GD03704	DC..	1A		YC067-YD157
0187	22		PA		1-7	21-31-22	D13688		C3		GD03704	DC..	1A		YD158-YR328
0188	22		PA		2-0	21-31-22	D13688		C1		GD03704	DC..	1A		YC053, YC055
0188	22		GA		2-0	21-31-22	D13688		C1		GD03704	DC..	1A		YC060-YC064
0188	22		PA		1-8	21-31-22	D13688		C1		GD03704	DC..	1A		YC067-YD157
0188	22		PA		1-7	21-31-22	D13688		C1		GD03704	DC..	1A		YD158-YR328
0189	22		PA		2-0	21-31-22	D13688		B3		GD03704	DC..	1A		YC053, YC055
0189	22		PA		1-8	21-31-22	D13688		B3		GD03704	DC..	1A		YC060-YC064, YC067-YD157
0189	22		PA		1-7	21-31-22	D13688		B3		GD03704	DC..	1A		YD158-YR328
0190	22		PA		2-0	21-31-22	D13688		B1		GD03704	DC..	1A		YC053, YC055
0190	22		GA		2-0	21-31-22	D13688		B1		GD03704	DC..	1A		YC060-YC064
0190	22		PA		1-8	21-31-22	D13688		B1		GD03704	DC..	1A		YC067-YD157
0190	22		PA		1-7	21-31-22	D13688		B1		GD03704	DC..	1A		YD158-YR328
0191	22		PA		2-0	21-31-22	D13688		A1		GD03704	DC..	1A		YC053, YC055
0191	22		GA		2-0	21-31-22	D13688		A1		GD03704	DC..	1A		YC060-YC064
0191	20		PA		1-8	21-31-22	D13688		A1		GD03704	DC..	1A		YC067-YD157
0191	20		PA		1-7	21-31-22	D13688		A1		GD03704	DC..	1A		YD158-YR328
0192	20		PA		2-0	21-31-22	D13688		X1		D40878J		3		YC053, YC055
0192	20		GA		2-0	21-31-22	D13688		X1		D40878J		3		YC060-YC064
0192	20		PA		1-5	21-31-22	D13688		X1		D40878J		3		YC067-YR328
0193	24		G6		2-0	21-31-23	D40884J		12		D13690		C2		YC053, YC055, YC060-YC064
0193	24		G6		1-2	21-31-23	D40884J		12		D13690		C2		YC067-YR328
0194	24		G6		2-0	21-31-23	D40884J		13		D13690		B2		YC053, YC055, YC060-YC064
0194	24		G6		1-2	21-31-23	D40884J		13		D13690		B2		YC067-YR328
0195	20		G5		2-0	21-31-23	D13690		A2		TB0028Y	A003	1A		YC053, YC055
0195	20		G5		2-0	21-31-23	D13690		A2		TB0030Y	A003	1A		YC060-YC064
0195	20		G5		1-7	21-31-23	D13690		A2		TB0028Y	A003	1A		YC067-YR328
0196	20		G5		2-0	21-31-23	D13690		X2		TB0028Y	A003	1A		YC053, YC055
0196	20		G5		2-0	21-31-23	D13690		X2		TB0030Y	A003	1A		YC060-YC064
0196	20		G5		1-7	21-31-23	D13690		X2		TB0028Y	A003	1A		YC067-YR328
0197	22		G5		2-0	21-31-23	D13690		C3		GD03704	DC..	1A		YC053, YC055, YC060-YC064
0197	22		G5		1-6	21-31-23	D13690		C3		GD03704	DC..	1A		YC067-YR328
0198	22		G5		2-0	21-31-23	D13690		C1		GD03704	DC..	1A		YC053, YC055, YC060-YC064
0198	22		G5		1-6	21-31-23	D13690		C1		GD03704	DC..	1A		YC067-YR328

WIRE LIST

D280A108

91-21-11

Section W0070

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0074	286A0074				J20 JUNCTION BOX-PLATE A (continued)										
0199	22		G5		2-0	21-31-23	D13690		B3		GD03704	DC..	1A		YC053, YC055
0199	22		G5		1-6	21-31-23	D13690		B3		GD03704	DC..	1A		YC060-YC064, YC067-YR328
0200	22		G5		2-0	21-31-23	D13690		B1		GD03704	DC..	1A		YC053, YC055, YC060-YC064
0200	22		G5		1-6	21-31-23	D13690		B1		GD03704	DC..	1A		YC067-YR328
0201	22		G5		2-0	21-31-23	D13690		A1		GD03704	DC..	1A		YC053, YC055, YC060-YC064
0201	20		G5		1-6	21-31-23	D13690		A1		GD03704	DC..	1A		YC067-YR328
0202	20		G5		2-0	21-31-23	D13690		X1		D40884J		14		YC053, YC055, YC060-YC064
0202	20		G5		1-2	21-31-23	D13690		X1		D40884J		14		YC067-YR328
0206	20		PA		1-6	47-30-11	D13842		2		D40884J		2		YC060-YC064
0206	20		PA		1-6	47-30-11	D13842		2		D40884J		10		YD160-YR328
0207	20		PA		1-7	47-30-11	D13842		5		GD03704	DC..	1A		YC060-YC064, YD160-YR328
0208	20		PA		1-6	28-44-11	D13842		7		D40884J		1		YC060-YC064
0208	20		PA		1-6	28-44-11	D13842		7		D40884J		6		YD160-YR328
0209	20		PA		1-7	28-44-11	D13842		3		GD03704	DC..	1A		YC060-YC064, YD160-YR328
W0076	286A0076				J22 JUNCTION BOX (CONTAINS ENGINE 1 WIRING)										
0005	20		PA		1-7	52-71-13	SM00001		9		D12756		A2		YC051-YD157
0005	20		PA		1-9	52-71-13	SM00001		9		D12756		A2		YD158-YD170
0005	20		PA		1-5	52-71-13	TB0022Y	B003	1A		D12756		A2		YL951-YL999, YR301-YR328
0005	20		PA		1-6	52-71-13	TB0022Y	B019	1A		D12756		A2		YN231-YN236, YN501
0006	20		PA		1-7	52-71-13	SM00001		9		D12756		X1		YC051-YD157
0006	20		PA		1-9	52-71-13	SM00001		9		D12756		X1		YD158-YD170
0006	20		PA		1-5	52-71-13	TB0022Y	B003	1A		D12756		X1		YL951-YL999, YR301-YR328
0006	20		PA		1-6	52-71-13	TB0022Y	B019	1A		D12756		X1		YN231-YN236, YN501
0007	20		PA		1-6	52-71-13	D40666J		26		SM00001		9		YC051-YD170
0007	20		PA		2-8	52-71-13	D40666J		26		TB0022Y	B003	1A		YL951-YL999, YR301-YR328
0007	20		PA		2-9	52-71-13	D40666J		26		TB0022Y	B019	1A		YN231-YN236, YN501
0008	20		PA		2-2	52-71-13	D40676J		3		D12756		X2		YC051-YD157
0008	20		PA		2-5	52-71-13	D40676J		3		D12756		X2		YD158-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0070

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0076	286A0076				J22 JUNCTION BOX (CONTAINS ENGINE 1 WIRING) (continued)										
0009	20		PA		1-7	52-71-13	TB0022Z	B017	1A		D12756	A1			YC051-YD157
0009	20		PA		1-6	52-71-13	TB0022Z	B017	1A		D12756	A1			YD158-YL999, YR301-YR328
0009	20		PA		1-6	52-71-13	TB0022Y	B017	1A		D12756	A1			YN231-YN236, YN501
0010	20		PA		2-1	52-71-13	D12538	A2			GD00532	DC..	1A		YC051-YD157
0010	20		PA		1-11	52-71-13	D12538	A2			GD00532	DC..	1A		YD158-YN236, YN501-YR328
0018	20		PA		2-1	52-71-13	D12538	B2			GD00532	DC..	1A		YC051-YD157
0018	20		PA		1-11	52-71-13	D12538	B2			GD00532	DC..	1A		YD158-YN236, YN501-YR328
0019	20		PA		1-8	52-71-13	TB0022Z	A017	1A		D12538	A1			YC051-YD157
0019	20		PA		1-7	52-71-13	TB0022Z	A017	1A		D12538	A1			YD158-YL999, YR301-YR328
0019	20		PA		1-7	52-71-13	TB0022Y	A017	1A		D12538	A1			YN231-YN236, YN501
0020	20		PA		2-4	52-71-13	D40676J	6			D12538	B1			YC051-YD157
0020	20		PA		2-7	52-71-13	D40676J	6			D12538	B1			YD158-YN236, YN501-YR328
0028	24		G6		1-8	73-22-31	D12538	X1			TB0032Y	B003	1A		YC051-YD157
0028	24		G6		1-7	73-22-31	D12538	X1			TB0032Y	B003	1A		YD158-YN236
0028	24		G6		1-6	73-22-31	D12538	X1			TB0022Z	A005	1A		YN501-YR328
0029	24		G6		1-5	73-22-31	D12538	X2			TB0022Y	A001	1A		YC051-YD157
0029	24		G6		1-6	73-22-31	D12538	X2			TB0022Y	A001	1A		YD158-YN236, YN501-YR328
0030	24		G6		2-3	73-22-31	D40670J	25			TB0022Y	A001	1A		YC051-YD157
0030	24		G6		2-6	73-22-31	D40670J	25			TB0022Y	A001	1A		YD158-YN236, YN501-YR328
0048	24		PK		2-6	34-49-11	D10849	7			SM00003		9		YC053-YD157
0048	24		PK		2-8	34-49-11	D10849	7			SM00003		9		YD158-YD170
0048	24		PK		1-9	34-49-11	D10849	7			TB0032Z	A021	1A		YL951-YN236, YN501-YR328
0049	24		PK		1-0	34-49-11	D40680J	9			SM00003		9		YC053-YD157
0049	24		PK		0-11	34-49-11	D40680J	9			SM00003		9		YD158-YD170
0049	24		PK		2-8	34-49-11	D40680J	9			TB0032Z	A021	1A		YL951-YN236, YN501-YR328
0050	24		PK		2-8	34-49-11	D10849	8			D40680J	13			YC053-YD157
0050	24		PK		2-10	34-49-11	D10849	8			D40680J	13			YD158-YN236, YN501-YR328
0051	22		PA		1-5	23-22-11	D02775	X1			TB0032Y	A003	1A		YC051-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0070

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0076	286A0076			J22 JUNCTION BOX (CONTAINS ENGINE 1 WIRING) (continued)											
0052	22		PA		3-2	23-22-11	D02775		X2		D40670J		2		YC051-YD157
0052	22		PA		3-3	23-22-11	D02775		X2		D40670J		2		YD158-YN236, YN501-YR328
0053	22		PA		3-2	23-22-11	D02775		A1		D40670J		3		YC051-YD157
0053	22		PA		3-3	23-22-11	D02775		A1		D40670J		3		YD158-YN236, YN501-YR328
0054	22		PA		1-5	23-22-11	D02775		A2		TB0032Y	A003	1A		YC051-YD157 YN501-YR328
0055	22		PA		2-11	23-22-11	D40670J		1		TB0032Y	A003	1A		YC051-YD157
0055	22		PA		3-2	23-22-11	D40670J		1		TB0032Y	A003	1A		YD158-YN236, YN501-YR328
0056	22		PA		3-1	23-22-11	D40666J		6		TB0032Y	A003	1A		YC051-YD157
0056	22		PA		3-4	23-22-11	D40666J		6		TB0032Y	A003	1A		YD158-YN236, YN501-YR328
0057	24		PK		2-8	34-49-11	D10849		6		D40680J		14		YC053-YD157
0057	24		PK		2-10	34-49-11	D10849		6		D40680J		14		YD158-YN236, YN501-YR328
0058	24		PK		1-3	34-49-11	D40680J		15		D40147J		23		YC053-YN236, YN501-YR328
0059	24		PK		1-0	34-49-11	SM00003		9		D40668J		16		YC053-YD170
0059	24		PK		3-0	34-49-11	TB0032Z	A021	1A		D40668J		16		YL951-YN236, YN501-YR328
0060	24		PK		1-0	34-49-11	SM00003		9		D40668J		17		YC053-YD170
0060	24		PK		3-0	34-49-11	TB0032Z	A021	1A		D40668J		17		YL951-YN236, YN501-YR328
0061	24		B6		1-10	32-31-11	D40668J		9		D11018		X1		YC051-YD157
0061	24		B6		1-11	32-31-11	D40668J		9		D11018		X1		YD158-YN236, YN501-YR328
0062	24		B6		2-2	32-31-11	D40670J		31		D11018		X2		YC051-YD157
0062	24		B6		2-4	32-31-11	D40670J		31		D11018		X2		YD158-YN236, YN501-YR328
0063	24		PK		2-6	34-49-11	D10849		12		SM00003		9		YC053-YD157
0063	24		PK		2-8	34-49-11	D10849		12		SM00003		9		YD158-YD170
0063	24		PK		1-9	34-49-11	D10849		12		TB0032Z	A021	1A		YL951-YN236, YN501-YR328
0064	24		PK		1-7	34-41-11	D11012		C3		D40147J		13		YC053-YN236, YN501-YR328
0066	24		B6		2-6	21-43-21	D11018		C2		D40672J		10		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0070

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0076	286A0076				J22 JUNCTION BOX (CONTAINS ENGINE 1 WIRING) (continued)										
0066	24		B6		2-8	21-43-21	D11018		C2		D40672J		10		YD158-YN236, YN501-YR328
0067	24		B6		2-6	21-43-21	D11018		B3		D40672J		11		YC051-YD157
0067	24		B6		2-8	21-43-21	D11018		B3		D40672J		11		YD158
0068	24		B6		2-6	21-43-21	D40672J		15		D11018		C3		YC051-YD157
0068	24		B6		2-8	21-43-21	D40672J		15		D11018		C3		YD158
0069	24		B6		2-6	21-43-21	D40672J		16		D11018		B2		YC051-YD157
0069	24		B6		2-8	21-43-21	D40672J		16		D11018		B2		YD158-YL999, YR301-YR328
0069	24		PK		2-8	21-43-21	D11018		B2		D40672J		16		YN231-YN236, YN501
0071	24		PK		1-3	32-31-11	D11020		X1		TB0022Z		B005	1A	YC051-YN236, YN501-YR328
0072	24		PK		2-0	32-31-11	D11020		X2		D40670J		9		YC051-YD157
0072	24		PK		2-2	32-31-11	D11020		X2		D40670J		9		YD158-YN236, YN501-YR328
0073	24		PK		1-5	21-42-11	D11020		A1		TB0022Y		A013	1A	YC051-YD157
0073	24		PK		1-3	21-42-11	D11020		A1		TB0022Y		A013	1A	YD158-YN236, YN501-YR328
0074	24		PK		1-10	21-42-11	D11020		A2		D40676J		13		YC051-YD157
0074	24		PK		2-0	21-42-11	D11020		A2		D40676J		13		YD158-YN236, YN501-YR328
0075	24		PK		0-7	21-42-11	TB0022Y		A013	1A	TB0022Y		A015	1A	YC051-YN236, YN501-YR328
0076	24		PK		2-5	21-42-11	D40670J		23		TB0022Y		B013	1A	YC051-YD157
0076	24		PK		2-6	21-42-11	D40670J		23		TB0022Y		B013	1A	YD158-YN236, YN501-YR328
0077	24		PK		2-5	21-42-11	D40670J		24		TB0022Y		B015	1A	YC051-YD157
0077	24		PK		2-6	21-42-11	D40670J		24		TB0022Y		B015	1A	YD158-YN236, YN501-YR328
0078	20		PA		1-9	34-41-11	D40674J		9		TB0022Y		A003	1A	YC053-YD157
0078	20		PA		2-0	34-41-11	D40674J		9		TB0022Y		A003	1A	YD158-YN236, YN501-YR328
0079	20		PA		1-6	34-41-11	D40147J		10		TB0022Y		A003	1A	YC053-YD157
0079	20		PA		1-8	34-41-11	D40147J		10		TB0022Y		A003	1A	YD158-YN236, YN501-YR328
0080	20		PA		1-6	34-41-11	D40147J		11		TB0022Y		A003	1A	YC053-YD157
0080	20		PA		1-8	34-41-11	D40147J		11		TB0022Y		A003	1A	YD158-YN236, YN501-YR328
0081	24		PK		1-3	32-31-11	D11012		X1		TB0022Z		B005	1A	YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0070

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0076	286A0076				J22 JUNCTION BOX (CONTAINS ENGINE 1 WIRING) (continued)										
0081	24		PK		1-2	32-31-11	D11012		X1		TB0022Z	B005	1A		YD158-YN236, YN501-YR328
0082	24		PK		2-3	32-31-11	D40670J		10		D11012		X2		YC051-YD157
0082	24		PK		2-5	32-31-11	D40670J		10		D11012		X2		YD158-YN236, YN501-YR328
0086	22		PA		1-6	34-41-11	D11012		C2		GD00542	DC..	1A		YC051-YD157
0086	22		PA		1-5	34-41-11	D11012		C2		GD00542	DC..	1A		YD158-YN236, YN501-YR328
0087	24		PK		2-5	34-41-11	D11012		C3		D40666J		30		YC051-YC052
0091	24		PK		1-4	32-31-11	D11008		X1		TB0022Z	B005	1A		YC051-YD157
0091	24		PK		1-3	32-31-11	D11008		X1		TB0022Z	B005	1A		YD158-YN236, YN501-YR328
0092	24		PK		2-5	32-31-11	D11008		X2		D40670J		11		YC051-YD157
0092	24		PK		2-6	32-31-11	D11008		X2		D40670J		11		YD158-YN236, YN501-YR328
0093	22		PA		2-3	29-25-11	D11008		A2		D40676J		1		YC051-YD157
0093	22		PA		2-4	29-25-11	D11008		A2		D40676J		1		YD158-YN236, YN501-YR328
0094	18		PA		2-3	29-25-11	D11008		A3		D40676J		2		YC051-YD157
0094	18		PA		2-4	29-25-11	D11008		A3		D40676J		2		YD158-YN236, YN501-YR328
0100	22		PA		1-11	34-41-11	D40670J		21		D40147J		1		YC053-YD157
0100	22		PA		2-0	34-41-11	D40670J		21		D40147J		1		YD158-YN236, YN501-YR328
0101	24		PK		1-8	32-31-11	D11022		X1		TB0022Z	B005	1A		YC051-YN236, YN501-YR328
0102	24		PK		2-9	32-31-11	D40670J		12		D11022		X2		YC051-YD157
0102	24		PK		2-11	32-31-11	D40670J		12		D11022		X2		YD158-YN236, YN501-YR328
0103	20		PA		2-11	30-71-11	D11022		A1		D40666J		13		YC051-YD157
0103	20		PA		3-1	30-71-11	D11022		A1		D40666J		13		YD158-YN236, YN501-YR328
0104	20		PA		2-7	30-71-11	D11022		A2		D40676J		10		YC051-YD157
0104	20		PA		2-9	30-71-11	D11022		A2		D40676J		10		YD158-YN236, YN501-YR328
0105	20		PA		2-11	30-71-11	D11022		A3		D40666J		10		YC051-YD157
0105	20		PA		3-1	30-71-11	D11022		A3		D40666J		10		YD158-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0070

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0076	286A0076				J22 JUNCTION BOX (CONTAINS ENGINE 1 WIRING) (continued)										
0111	24		PK		1-5	32-31-11	D11002		X1		TB0022Z	B005	1A		YC051-YN236, YN501-YR328
0112	24		PK		2-6	32-31-11	D40670J		13		D11002		X2		YC051-YD157
0112	24		PK		2-7	32-31-11	D40670J		13		D11002		X2		YD158-YN236, YN501-YR328
0113	20		PA		1-6	78-34-11	D11002		A2		TB0022Y	B011	1A		YC051-YD157
0113	20		PA		1-5	78-34-11	D11002		A2		TB0022Y	B011	1A		YD158-YN236, YN501-YR328
0114	20		PA		2-2	78-34-11	D40676J		14		TB0022Y	B011	1A		YC051-YD157
0114	20		PA		2-3	78-34-11	D40676J		14		TB0022Y	B011	1A		YD158-YN236, YN501-YR328
0115	20		PA		1-4	78-34-11	D11002		A3		GD00542	DC..	1A		YC051-YD157
0115	20		PA		1-3	78-34-11	D11002		A3		GD00542	DC..	1A		YD158-YN236, YN501-YR328
0117	20		PA		1-3	23-11-16	D11002		B2		GD00542	DC..	1A		YD158-YD170
0118	22		PA		1-11	34-41-11	D40670J		22		D40147J		2		YC053-YD157
0118	22		PA		2-0	34-41-11	D40670J		22		D40147J		2		YD158-YN236, YN501-YR328
0121	24		PK		1-2	73-22-31	D10918		X1		TB0032Y	B003	1A		YC051-YN236
0121	24		PK		1-8	73-22-31	D10918		X1		TB0022Z	A005	1A		YN501-YR328
0122	24		G6		1-9	73-22-31	D10918		X2		TB0022Y	A001	1A		YC051-YN236, YN501-YR328
0123	24		PK		3-1	73-22-31	D40666J		15		TB0032Y	B003	1A		YC051-YD157
0123	24		PK		3-4	73-22-31	D40666J		15		TB0032Y	B003	1A		YD158-YN236
0123	24		PK		2-7	73-22-31	D40666J		15		TB0022Z	A005	1A		YN501-YR328
0124	22		PA		2-6	29-23-11	D10918		A1		D40668J		7		YC051-YD157
0124	22		PA		2-7	29-23-11	D10918		A1		D40668J		7		YD158-YN236, YN501-YR328
0125	24		PK		1-4	73-22-31	D10918		A2		GD00542	DC..	1A		YC051-YD157
0125	24		PK		1-3	73-22-31	D10918		A2		GD00542	DC..	1A		YD158-YN236, YN501-YR328
0126	24		G6		2-10	73-22-31	D10918		A3		D40670J		26		YC051-YD157
0126	24		G6		2-11	73-22-31	D10918		A3		D40670J		26		YD158-YN236, YN501-YR328
0127	22		PA		1-10	31-31-11	D10918		C1		TB0022Y	A011	1A		YC051-YD157
0127	22		PA		1-8	31-31-11	D10918		C1		TB0022Y	A011	1A		YD158-YN236, YN501-YR328
0128	22		PA		1-4	31-31-11	D10918		C2		GD00542	DC..	1A		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0070

Page 15

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0076	286A0076				J22 JUNCTION BOX (CONTAINS ENGINE 1 WIRING) (continued)										
0128	22		PA		1-3	31-31-11	D10918		C2		GD00542	DC..	1A		YD158-YN236, YN501-YR328
0129	22		PA		1-4	34-41-11	D10918		D1		GD00542	DC..	1A		YC051-YC052
0130	24		PK		3-0	34-41-11	D10918		D2		D40666J	25			YC051-YC052
0131	24		PK		1-9	76-21-11	D10922		X1		TB0022Y	A009	1A		YC051-YD157
0131	24		PK		1-7	76-21-11	D10922		X1		TB0022Y	A009	1A		YD158-YN236, YN501-YR328
0132	24		PK		2-10	76-21-11	D10922		X2		D40666J	18			YC051-YD157
0132	24		PK		3-0	76-21-11	D10922		X2		D40666J	18			YD158-YN236, YN501-YR328
0135	24		PK		2-8	31-31-15	D10922		B2		D40670J	4			YC051-YD157
0135	24		PK		2-10	31-31-15	D10922		B2		D40670J	4			YD158-YN236, YN501-YR328
0136	24		PK		1-9	31-31-15	D10922		B1		TB0022Y	B009	1A		YC051-YD157
0136	24		PK		1-7	31-31-15	D10922		B1		TB0022Y	B009	1A		YD158-YN236, YN501-YR328
0137	24		PK		2-8	76-21-11	D10922		C2		D40670J	27			YC051-YD157
0137	24		PK		2-10	76-21-11	D10922		C2		D40670J	27			YD158-YN236, YN501-YR328
0138	20		PA		1-2	76-21-11	D10922		C3		GD00542	DC..	1A		YC051-YN236, YN501-YR328
0139	20		G5		1-9	78-34-11	D40674J		3		TB0022Y	B001	1A		YC051-YD157
0139	20		G5		2-0	78-34-11	D40674J		3		TB0022Y	B001	1A		YD158-YN236, YN501-YR328
0140	20		G5		1-9	78-34-11	D40674J		4		TB0022Y	B001	1A		YC051-YD157
0140	20		G5		2-0	78-34-11	D40674J		4		TB0022Y	B001	1A		YD158-YN236, YN501-YR328
0141	24		PK		1-9	76-21-11	D10922		Y1		TB0022Y	A009	1A		YC051-YD157
0141	24		PK		1-7	76-21-11	D10922		Y1		TB0022Y	A009	1A		YD158-YN236, YN501-YR328
0142	24		PK		2-10	76-21-11	D10922		Y2		D40666J	17			YC051-YD157
0142	24		PK		3-0	76-21-11	D10922		Y2		D40666J	17			YD158-YN236, YN501-YR328
0143	22		PA		2-5	23-15-15	D40666J		27		TB0022Z	A005	1A		YC051-YD157
0145	22		PA		2-1	23-15-15	TB0022Z		A005	1A	D10085	A2			YC051-YD157
0146	22		PA		2-1	23-15-15	TB0022Z		A005	1A	D10085	X1			YC051-YD157
0147	22		PA		3-6	23-15-15	D10085		X2		D40672J	21			YC051-YD157
0148	22		PA		3-6	23-15-15	D10085		A1		D40672J	22			YC051-YD157
0149	24		PK		1-6	34-49-11	D40680J		22		D40668J	19			YC053-YD157

WIRE LIST

D280A108

91-21-11

Section W0070

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0076	286A0076				J22 JUNCTION BOX (CONTAINS ENGINE 1 WIRING) (continued)										
0149	24		PK		1-5	34-49-11	D40680J		22		D40668J		19		YD158-YN236, YN501-YR328
0150	24		PK		1-6	34-49-11	D40680J		23		D40668J		18		YC053-YD157
0150	24		PK		1-5	34-49-11	D40680J		23		D40668J		18		YD158-YN236, YN501-YR328
0151	20		PA		2-7	23-11-16	D11002		B1		D40670J		28		YD158-YD170
0152	22		PA		1-6	78-32-51	D10634		X2		GD00542	DC..	1A		YC051-YN236, YN501-YR328
0153	18		CQ		1-5	78-32-51	D10634		A1		TB0032V	B013	1		YC051-YD157
0153	18		CQ		1-4	78-32-51	D10634		A1		TB0032V	B013	1		YD158-YN236, YN501-YR328
0154	22		PA		2-6	23-71-01	D40666J		29		SM00004		9		YC051-YC052
0154	22		PA		1-6	23-71-01	D40666J		29		SM00004		9		YC053-YN236, YN501-YR328
0155	18		PA		1-6	78-32-51	D10634		A3		GD00542	DC..	1D		YC051-YN236, YN501-YR328
0156	18		CQ		1-5	78-32-51	D10634		B1		TB0032V	B013	1		YC051-YD157
0156	18		CQ		1-4	78-32-51	D10634		B1		TB0032V	B013	1		YD158-YN236, YN501-YR328
0157	18		PA		1-6	78-32-51	D10634		B3		GD00542	DC..	1D		YC051-YN236, YN501-YR328
0158	20		PA		1-11	23-71-01	D11073		X2		GD00522	DC..	1		YC051-YD157
0158	20		PA		1-8	23-71-01	D11073		X2		GD00522	DC..	1		YD158-YN236, YN501-YR328
0159	20		PA		1-8	23-71-01	D12538		C2		GD00522	DC..	1		YC051-YN236, YN501-YR328
0160	22		PA		2-5	26-23-11	D40674J		10		D11022		D1		YD158-YD170, YR315-YR316, YR319
0160	22		PA		2-5	SPARE	D40674J		10		D11022		D1		YR317
0161	20		PA		1-8	26-23-11	D11022		D2		GD00532	DC..	1A		YD158-YD170, YR315-YR316, YR319
0161	20		PA		1-8	SPARE	D11022		D2		GD00532	DC..	1A		YR317
0162	22		PA		1-0	78-32-51	D03527		X2		M01666	A	C		YC051-YD157
0162	22		PA		1-1	78-32-51	D03527		X2		M01666	A	C		YD158-YN236, YN501-YR328
0163	20		PA		2-0	78-34-11	D03527		A1		TB0022Y	B001	1A		YC051-YN236, YN501-YR328
0164	20		PA		2-1	78-34-11	D03527		A2		TB0022Y	B011	1A		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0070

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0076	286A0076				J22 JUNCTION BOX (CONTAINS ENGINE 1 WIRING) (continued)										
0164	20		PA		2-0	78-34-11	D03527	A2			TB0022Y	B011	1A		YD158-YN236, YN501-YR328
0165	22		PA		2-11	23-71-01	SM00004		9		D11073	X1			YC051-YC052
0165	22		PA		1-11	23-71-01	SM00004		9		D11073	X1			YC053-YN236, YN501-YR328
0166	22		PA		2-11	23-71-01	D40666J		31		D11073	A2			YC051-YN236, YN501-YR328
0167	22		PA		1-0	23-71-01	D40668J		31		SM00005		9		YC051-YN236, YN501-YR328
0168	22		PA		1-8	23-71-01	D12538		C1		SM00005		9		YC051-YD157
0168	22		PA		1-11	23-71-01	D12538		C1		SM00005		9		YD158-YN236, YN501-YR328
0169	22		PA		1-11	23-71-01	D11073		C1		SM00005		9		YC051-YN236, YN501-YR328
0170	22		PA		3-1	23-71-01	SM00006		9		D40672J	23			YC051-YC052
0170	22		PA		1-8	23-71-01	SM00006		9		D40672J	23			YC053-YN236, YN501-YR328
0171	22		PA		2-11	23-71-01	D11073		A1		SM00006		9		YC051-YC052
0171	22		PA		1-11	23-71-01	D11073		A1		SM00006		9		YC053-YN236, YN501-YR328
0172	22		PA		1-7	78-32-51	D10636		X2		GD00542	DC..	1A		YC051-YD157
0172	22		PA		1-4	78-32-51	D10636		X2		GD00542	DC..	1A		YD158-YN236, YN501-YR328
0173	22		PA		1-2	78-32-51	D10634		Y2		D10636	A1			YC051-YN236, YN501-YR328
0174	22		PA		1-7	78-32-51	D10636		A2		GD00542	DC..	1A		YC051-YD157
0174	22		PA		1-4	78-32-51	D10636		A2		GD00542	DC..	1A		YD158-YN236, YN501-YR328
0177	22		PA		2-8	23-71-01	D40672J		9		SM00006		9		YC051-YC052
0177	22		PA		1-8	23-71-01	D40672J		9		SM00006		9		YC053-YN236, YN501-YR328
0178	22		PA		3-5	23-71-01	D40672J		12		D11131	A1			YC051-YC052
0178	22		PA		2-5	23-71-01	D40672J		12		D11131	A1			YC053-YD157
0178	22		PA		2-7	23-71-01	D40672J		12		D11131	A1			YD158-YN236, YN501-YR328
0179	22		PA		1-11	23-71-01	D40668J		6		D11131	X2			YC051-YC052, YD158-YN236, YN501-YR328
0179	22		PA		1-9	23-71-01	D40668J		6		D11131	X2			YC053-YD157

WIRE LIST

D280A108

91-21-11

Section W0070

Page 18

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0076	286A0076				J22 JUNCTION BOX (CONTAINS ENGINE 1 WIRING) (continued)										
0180	22		PA		2-7	23-71-01	D11131	A2			D12538	C3			YC051-YC052
0180	22		PA		1-7	23-71-01	D11131	A2			D12538	C3			YC053-YN236, YN501-YR328
0181	22		PA		2-3	23-71-01	SM00004		9		D11131	X1			YC051-YC052
0181	22		PA		1-3	23-71-01	SM00004		9		D11131	X1			YC053-YD157
0181	22		PA		1-5	23-71-01	SM00004		9		D11131	X1			YD158-YN236, YN501-YR328
0182	24		PK		1-1	34-41-11	D40147J	28			SM00003		9		YC053-YD157
0182	24		PK		1-2	34-41-11	D40147J	28			SM00003		9		YD158-YD170
0182	24		PK		2-6	34-41-11	D40147J	28			TB0032Z	A021	1A		YL951-YN236, YN501-YR328
0183	24		PK		1-3	34-41-11	D40680J	24			D40147J	27			YC053-YN236, YN501-YR328
0184	22		PA		2-3	34-41-11	D40147J	25			D40672J	17			YC053-YD157
0184	22		PA		2-4	34-41-11	D40147J	25			D40672J	17			YD158-YN236, YN501-YR328
0185	22		PA		1-3	34-41-11	D40147J	26			D40680J	25			YC053-YN236, YN501-YR328
0191	24		PK		1-5	73-22-11	D10954	X1			TB0032Y	B003	1A		YC051-YN236
0191	24		PK		2-1	73-22-11	D10954	X1			TB0022Z	A005	1A		YN501-YR328
0192	24		PK		3-4	73-22-11	D40666J	7			D10954	X2			YC051-YD157
0192	24		PK		3-6	73-22-11	D40666J	7			D10954	X2			YD158-YN236, YN501-YR328
0194	20		PA		3-4	73-22-11	D10954	A2			D40666J	14			YC051-YD157
0194	20		PA		3-6	73-22-11	D10954	A2			D40666J	14			YD158-YN236, YN501-YR328
0196	20		G5		2-8	73-22-11	D10954	B2			D40674J	12			YC051-YD157
0196	20		G5		2-9	73-22-11	D10954	B2			D40674J	12			YD158-YN236, YN501-YR328
0199	24		G6		1-4	73-22-31	TB0022Y	A001	1A		D13130	X2			YN501-YR328
0200	24		G6		1-3	73-22-31	TB0022Z	A005	1A		D13130	X1			YN501-YR328
0201	24		PK		3-4	32-41-11	D11404	6			D40670J	19			YC051-YD157
0201	24		PK		3-7	32-41-11	D11404	6			D40670J	19			YD158-YN236, YN501-YR328
0202	24		PK		1-8	32-41-11	D11404	12			TB0032Y	B001	1A		YC051-YN236, YN501-YR328
0203	24		PK		2-11	32-41-11	D40670J	15			TB0032Y	B001	1A		YC051-YD157
0203	24		PK		3-2	32-41-11	D40670J	15			TB0032Y	B001	1A		YD158-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0070

Page 19

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0076	286A0076				J22 JUNCTION BOX (CONTAINS ENGINE 1 WIRING) (continued)										
0204	24		PK		3-4	32-41-11	D11404				D40670J	18			YC051-YD157
0204	24		PK		3-7	32-41-11	D11404				D40670J	18			YD158-YN236, YN501-YR328
0205	24		PK		1-8	32-41-11	D11404				TB0032Y	A001	1A		YC051-YN236, YN501-YR328
0211	24		PK		3-4	32-41-11	D11406				D40670J	16			YC051-YD157
0211	24		PK		3-7	32-41-11	D11406				D40670J	16			YD158-YN236, YN501-YR328
0212	24		PK		1-8	32-41-11	D11406				TB0032Y	B001	1A		YC051-YN236, YN501-YR328
0213	22		PA		1-2	27-62-11	D11406				GD00532	DC..	1A		YC051-YN236, YN501-YR328
0214	22		PA		3-4	27-62-11	D11406				D40670J	29			YC051-YD157
0214	22		PA		3-7	27-62-11	D11406				D40670J	29			YD158-YN236, YN501-YR328
0215	24		PK		1-8	32-41-11	D11406				TB0032Y	A001	1A		YC051-YN236, YN501-YR328
0216	24		PK		2-7	32-41-11	D40668J				TB0032Y	A001	1A		YC051-YD157
0216	24		PK		2-10	32-41-11	D40668J				TB0032Y	A001	1A		YD158-YN236, YN501-YR328
0217	24		PK		2-11	32-41-11	D40670J				TB0032Y	A001	1A		YC051-YD157
0217	24		PK		3-2	32-41-11	D40670J				TB0032Y	A001	1A		YD158-YN236, YN501-YR328
0218	24		PK		1-2	32-41-11	D11406				GD00532	DC..	1A		YC051-YN236, YN501-YR328
0251	22		PA		3-2	21-25-11	R00429		X1	C	D40666J	8			YC051-YD157
0251	22		PA		3-3	21-25-11	R00429		X1	C	D40666J	8			YD158-YL999, YR301-YR328
0252	22		PA		2-9	21-25-11	R00429		X2	C	D40676J	12			YC051-YD157
0252	22		PA		2-10	21-25-11	R00429		X2	C	D40676J	12			YD158-YL999, YR301-YR328
0253	14		PA		3-7	21-25-11	R00429		A1	D	D40678J	4			YC051-YD157
0253	14		PA		3-8	21-25-11	R00429		A1	D	D40678J	4			YD158-YL999, YR301-YR328
0254	14		PA		3-7	21-25-11	R00429		A2	D	D40678J	1			YC051-YD157
0254	14		PA		3-8	21-25-11	R00429		A2	D	D40678J	1			YD158-YL999, YR301-YR328
0255	14		PA		3-6	21-25-11	R00429		B1	D	D40678J	5			YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0070

Page 20

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W0076	286A0076				J22 JUNCTION BOX (CONTAINS ENGINE 1 WIRING) (continued)											
0255	14		PA		3-8	21-25-11		R00429	B1	D		D40678J	5			YD158-YL999, YR301-YR328
0256	14		PA		3-6	21-25-11		R00429	B2	D		D40678J	2			YC051-YD157
0256	14		PA		3-7	21-25-11		R00429	B2	D		D40678J	2			YD158-YL999, YR301-YR328
0257	14		PA		3-7	21-25-11		R00429	C1	D		D40678J	6			YC051-YL999, YR301-YR328
0258	14		PA		3-6	21-25-11		R00429	C2	D		D40678J	3			YC051-YD157
0258	14		PA		3-7	21-25-11		R00429	C2	D		D40678J	3			YD158-YL999, YR301-YR328
0261	22		PA		2-11	27-62-11		D10571	X1			D40672J	13			YC051-YD157
0261	22		PA		3-3	27-62-11		D10571	X1			D40672J	13			YD158-YN236, YN501-YR328
0262	22		PA		2-11	27-62-11		D10571	X2			D40672J	14			YC051-YD157
0262	22		PA		3-3	27-62-11		D10571	X2			D40672J	14			YD158-YN236, YN501-YR328
0263	22		PA		2-3	27-62-11		D10571	A1			D40668J	12			YC051-YD157
0263	22		PA		2-7	27-62-11		D10571	A1			D40668J	12			YD158-YN236, YN501-YR328
0264	22		PA		2-0	27-62-11		D10571	A2			GD00532	DC..	1A		YC051-YD157
0264	22		PA		1-9	27-62-11		D10571	A2			GD00532	DC..	1A		YD158-YN236, YN501-YR328
0266	22		PA		2-3	27-62-11		D10571	B1			D40668J	11			YC051-YD157
0266	22		PA		2-7	27-62-11		D10571	B1			D40668J	11			YD158-YN236, YN501-YR328
0267	22		PA		2-3	27-62-11		D10571	B2			D40668J	13			YC051-YD157
0267	22		PA		2-7	27-62-11		D10571	B2			D40668J	13			YD158-YN236, YN501-YR328
0268	22		PA		2-0	27-62-11		D10571	B3			GD00532	DC..	1A		YC051-YD157
0268	22		PA		1-9	27-62-11		D10571	B3			GD00532	DC..	1A		YD158-YN236, YN501-YR328
0270	22		PA		2-3	27-62-11		D10571	C2			D40668J	14			YC051-YD157
0270	22		PA		2-7	27-62-11		D10571	C2			D40668J	14			YD158-YN236, YN501-YR328
0271	22		PA		2-3	27-62-11		D10571	C3			D40668J	15			YC051-YD157
0271	22		PA		2-7	27-62-11		D10571	C3			D40668J	15			YD158-YN236, YN501-YR328
0272	20		PA		1-7	78-34-11		D10571	D1			TB0022Y	B011	1A		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0070

Page 21

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0076	286A0076				J22 JUNCTION BOX (CONTAINS ENGINE 1 WIRING) (continued)										
0272	20	PA			1-8	78-34-11	D10571	D1			TB0022Y	B011	1A		YD158-YN236, YN501-YR328
0274	20	PA			1-5	78-34-11	D10571	D2			GD00542	DC..	1A		YC051-YD157
0274	20	PA			1-2	78-34-11	D10571	D2			GD00542	DC..	1A		YD158-YN236, YN501-YR314
0274	20	PA			1-3	78-34-11	D10571	D2			GD00542	DC..	1A		YR315-YR328
0275	24	PK			1-6	34-61-26	D40674J	5			D11020	B2			YC059-YD157
0275	24	PK			1-8	34-61-26	D40674J	5			D11020	B2			YD158-YN236, YN501-YR328
0276	20	PA			2-4	34-61-26	D11020	B3			GD00532	DC..	1A		YC059-YN236, YN501-YR328
0277	24	PK			1-6	34-61-26	D40674J	6			D11020	C2			YC059-YD157
0277	24	PK			1-8	34-61-26	D40674J	6			D11020	C2			YD158-YN236, YN501-YR328
0278	20	PA			2-4	34-61-26	D11020	C3			GD00532	DC..	1A		YC059-YN236, YN501-YR328
0303	22	CQ			3-5	78-32-51	D40672J	2			TB0032V	A013	1		YC051-YD157
0303	22	CQ			3-6	78-32-51	D40672J	2			TB0032V	A013	1		YD158
0303	22	CQ			1-8	78-32-51	D40672J	2			SM00011		9		YL951-YN236, YN501-YR328
0304	22	CQ			1-6	78-32-51	D10636	X1			TB0032V	A013	1		YC051-YD157
0304	22	CQ			1-2	78-32-51	D10636	X1			TB0032V	A013	1		YD158
0304	22	CQ			2-2	78-32-51	D10636	X1			SM00011		9		YL951-YN236, YN501-YR328
0305	22	CQ			1-5	78-32-51	D10634	Y1			TB0032V	A013	1		YC051-YD157
0305	22	CQ			1-4	78-32-51	D10634	Y1			TB0032V	A013	1		YD158
0305	22	CQ			2-4	78-32-51	D10634	Y1			SM00011		9		YL951-YN236, YN501-YR328
0306	22	CQ			3-4	78-32-51	D10634	X1			D40672J	7			YC051-YD157
0306	22	CQ			3-6	78-32-51	D10634	X1			D40672J	7			YD158-YN236, YN501-YR328
0307	22	CQ			3-4	78-32-51	D40672J	6			TB0032W	B009	1		YC051-YD157
0307	22	CQ			3-6	78-32-51	D40672J	6			TB0032W	B009	1		YD158-YN236, YN501-YR328
0308	22	CQ			3-4	78-32-51	D40672J	8			TB0032W	A009	1		YC051-YD157
0308	22	CQ			3-6	78-32-51	D40672J	8			TB0032W	A009	1		YD158-YN236, YN501-YR328
0309	18	PA			1-0	78-32-51	TB0032W	B009	1		TB0032Y	B007	1D		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0070

Page 22

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type
W0076	286A0076			J22 JUNCTION BOX (CONTAINS ENGINE 1 WIRING) (continued)										
0309	18	PA		0-11	78-32-51	TB0032W	B009	1		TB0032Y	B007	1D		YD158-YN236, YN501-YR328
0310	18	PA		2-4	78-32-51	D40672J	18	18		GD00522	DC..	1		YC051-YD157
0310	18	PA		2-5	78-32-51	D40672J	18	18		GD00522	DC..	1		YD158-YN236, YN501-YR328
0311	18	PA		3-3	78-32-51	D40672J	30	18		TB0032Y	B005	1D		YC051-YD157
0311	18	PA		3-6	78-32-51	D40672J	30	18		TB0032Y	B005	1D		YD158-YN236, YN501-YR328
0312	18	PA		2-4	78-32-51	D40672J	20	18		GD00522	DC..	1		YC051-YD157
0312	18	PA		2-5	78-32-51	D40672J	20	18		GD00522	DC..	1		YD158-YN236, YN501-YR328
0313	18	PA		3-3	78-32-51	D40672J	19	18		TB0032Y	B007	1D		YC051-YD157
0313	18	PA		3-6	78-32-51	D40672J	19	18		TB0032Y	B007	1D		YD158-YN236, YN501-YR328
0314	22	CQ		1-5	78-32-51	D03527	X1			TB0032W	A009	1		YC051-YD157
0314	22	CQ		1-3	78-32-51	D03527	X1			TB0032W	A009	1		YD158-YN236, YN501-YR328
0315	18	CQ		1-4	78-32-51	D10634	A2			TB0032W	A009	1		YC051-YD157
0315	18	CQ		1-3	78-32-51	D10634	A2			TB0032W	A009	1		YD158-YN236, YN501-YR328
0316	18	CQ		1-4	78-32-51	D10634	B2			TB0032W	B009	1		YC051-YD157
0316	18	CQ		1-3	78-32-51	D10634	B2			TB0032W	B009	1		YD158-YN236, YN501-YR328
0317	18	PA		1-0	78-32-51	TB0032W	A009	1		TB0032Y	B005	1D		YC051-YD157
0317	18	PA		0-11	78-32-51	TB0032W	A009	1		TB0032Y	B005	1D		YD158-YN236, YN501-YR328
0338	20	PA		1-6	47-30-11	D10918	D2			GD00532	DC..	1A		YL951-YN236, YN501-YR328
0339	20	PA		2-5	47-30-11	D10918	D1			D40674J	8			YL951-YN236, YN501-YR328
0340	20	PA		2-1	47-30-11	D11002	D3			D40674J	11			YL951-YN236, YN501-YR328
0341	20	PA		1-10	47-30-11	D11002	D2			GD00532	DC..	1A		YL951-YN236, YN501-YR328
0342	22	PA		2-4	78-32-51	SM00011		9		TB0032V	A015	1		YL951-YN236, YN501-YR328
0344	22	PA		2-6	21-25-11	D40668J	32			D11012	B3			YC060-YC064
0344	22	PA		2-1	21-25-11	D40668J	32			D11012	B3			YL951-YN236, YN501-YR328

WIRE LIST
D280A108

91-21-11
Section W0070
Page 23
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W0076	286A0076				J22 JUNCTION BOX (CONTAINS ENGINE 1 WIRING) (continued)											
0345	22		PA		2-6	21-25-11		D40668J	33			D11012	A3			YC060-YC064
0345	22		PA		2-1	21-25-11		D40668J	33			D11012	A3			YL951-YN236, YN501-YR328
0346	22		PA		2-6	21-25-11		D40670J	32			D11012	B2			YC060-YC064
0346	22		PA		2-5	21-25-11		D40670J	32			D11012	B2			YL951-YN236, YN501-YR328
0347	22		PA		2-6	21-25-11		D40670J	33			D11012	A2			YC060-YC064
0347	22		PA		2-5	21-25-11		D40670J	33			D11012	A2			YL951-YN236, YN501-YR328
0348	24		B6		1-11	21-43-21		D40668J	34			D11018	B3			YL951-YN236, YN501-YR328
0349	24		B6		1-11	21-43-21		D40668J	42			D11018	C3			YL951-YN236, YN501-YR328
0350	18		PA		1-6	78-32-51		TB0032V	B015	1		GD00542	DC..	1D		YL951-YN236, YN501-YR328
0375	22		PA		2-9	31-35-03		D12538	D3			D40670J	5			YN236, YN501-YR328
0408	20		PA		1-11	31-35-03		D12538	D2			GD00532	DC..	1A		YN236, YN501-YR328
0413	20		PA		1-9	31-31-15		D10922	B3			GD00522	DC..	1		YL955-YL999, YN236, YN501-YR328
0414	22		PA		2-2	44-21-22		D13130	B2			D40668J	35			YN501-YR328
0415	22		PA		1-6	44-21-22		D13130	B3			GD00588	DC..	1A		YN501-YR328
0500	20		PA		2-4	52-71-13		D40676J	4			TB0022Z	B017	1A		YC051-YD157
0500	20		PA		2-5	52-71-13		D40676J	4			TB0022Z	B017	1A		YD158-YL999, YR301-YR328
0500	20		PA		2-5	52-71-13		D40676J	4			TB0022Y	B017	1A		YN231-YN236, YN501
0504	22		PA		2-6	31-31-11		D40666J	1			TB0022Y	B009	1A		YC051-YD157
0504	22		PA		2-7	31-31-11		D40666J	1			TB0022Y	B009	1A		YD158-YN236, YN501-YR328
0505	22		PA		2-6	31-31-11		D40666J	2			TB0022Y	A011	1A		YC051-YD157
0505	22		PA		2-7	31-31-11		D40666J	2			TB0022Y	A011	1A		YD158-YN236, YN501-YR328
0509	22		PA		2-0	31-31-11		D40668J	3			TB0022Y	B009	1A		YC051-YD157
0509	22		PA		2-1	31-31-11		D40668J	3			TB0022Y	B009	1A		YD158-YN236, YN501-YR328
0510	22		PA		2-0	31-31-11		D40668J	4			TB0022Y	A011	1A		YC051-YD157
0510	22		PA		2-1	31-31-11		D40668J	4			TB0022Y	A011	1A		YD158-YN236, YN501-YR328
0514	24		PK		2-3	32-31-11		D40670J	14			TB0022Z	B005	1A		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0070

Page 24

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0076	286A0076				J22 JUNCTION BOX (CONTAINS ENGINE 1 WIRING) (continued)										
0514	24		PK		2-5	32-31-11	D40670J	14			TB0022Z	B005	1A		YD158-YN236, YN501-YR328
0515	24		PK		2-6	76-21-11	D40666J	16			TB0022Y	A009	1A		YC051-YD157
0515	24		PK		2-7	76-21-11	D40666J	16			TB0022Y	A009	1A		YD158-YN236, YN501-YR328
0516	18		CQ		3-5	78-32-51	D40672J	1	18		TB0032V	B013	1		YC051-YD157
0516	18		CQ		3-6	78-32-51	D40672J	1	18		TB0032V	B013	1		YD158-YN236, YN501-YR328
0517	20		PA		2-4	52-71-13	D40676J	5			TB0022Z	A017	1A		YC051-YD157
0517	20		PA		2-5	52-71-13	D40676J	5			TB0022Z	A017	1A		YD158-YL999, YR301-YR328
0517	20		PA		2-5	52-71-13	D40676J	5			TB0022Y	A017	1A		YN231-YN236, YN501
0518	20		PA		1-8	52-71-13	TB0022Y	B021	1A		D12756	B1			YC051-YD157
0518	20		PA		1-7	52-71-13	TB0022Y	B021	1A		D12756	B1			YD158-YL999, YR301-YR328
0519	20		PA		0-11	52-71-13	TB0022Y	A021	1A		TB0022Z	A017	1A		YC051-YL999, YR301-YR314
0519	20		PA		1-4	52-71-13	TB0022Y	A021	1A		TB0022Z	A017	1A		YR315-YR328
0520	20		PA		2-5	52-71-13	TB0022Y	B021	1A		D40676J	7			YC051-YD157
0520	20		PA		2-6	52-71-13	TB0022Y	B021	1A		D40676J	7			YD158-YL999, YR301-YR328
0523	20		PA		1-7	52-71-13	SM00001		9		D12756	B2			YC051-YD157
0523	20		PA		1-9	52-71-13	SM00001		9		D12756	B2			YD158-YD170
0523	20		PA		1-5	52-71-13	TB0022Y	B003	1A		D12756	B2			YL951-YL999, YR301-YR328
0528	22		PA		1-2	78-32-51	M01666	B	C		GD00532	DC..	1A		YC051-YD157
0528	22		PA		1-4	78-32-51	M01666	B	C		GD00532	DC..	1A		YD158-YN236, YN501-YR328
0529	18		PA		1-5	78-32-51	TB0032Y	A005	1D		GD00542	ST..	1D		YC051-YN236, YN501-YR314
0529	18		PA		1-6	78-32-51	TB0032Y	A005	1D		GD00542	ST..	1D		YR315-YR328
0530	18		PA		1-5	78-32-51	TB0032Y	A007	1D		GD00542	DC..	1D		YC051-YN236, YN501-YR314
0530	18		PA		1-6	78-32-51	TB0032Y	A007	1D		GD00542	DC..	1D		YR315-YR328
1001	20		X1	AA	3-4	73-22-11	D10954	A1			D40666J	11			YC051-YD157
1001	20		X1	AA	3-6	73-22-11	D10954	A1			D40666J	11			YD158-YN236, YN501-YR328
1001Z				AA	0-0	73-22-11	GD00532	ST..	1A		D40666J	12			YC051-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0070

Page 25

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0076	286A0076			J22 JUNCTION BOX (CONTAINS ENGINE 1 WIRING) (continued)											
1002	20	X1	AB		2-8	73-22-11	D10954	B1			D40674J	13			YC051-YD157
1002	20	X1	AB		2-9	73-22-11	D10954	B1			D40674J	13			YD158-YN236, YN501-YR328
1002Z			AB		0-0	73-22-11	GD00532	ST..	1A		D40674J	14			YC051-YN236, YN501-YR328
2001B	24	Y2	GA		2-10	73-21-11	D10922	A2			D40666J	23			YC051-YD157
2001B	24	Y2	GA		3-0	73-21-11	D10922	A2			D40666J	23			YD158-YN236, YN501-YR328
2001R	24	Y2	GA		0-0	73-21-11	D10922	A1			D40666J	22			YC051-YN236, YN501-YR328
2001Z			GA		0-0	73-21-11	GD00542	ST..	1A		D40666J	24			YC051-YN236, YN501-YR328
2002B	24	7K	GB		2-8	34-49-11	D10849	4			D40680J	11			YC053-YD157
2002B	24	7K	GB		2-10	34-49-11	D10849	4			D40680J	11			YD158-YN236, YN501-YR328
2002W	24	7K	GB		0-0	34-49-11	D10849	2			D40680J	10			YC053-YN236, YN501-YR328
2002Z			GB		0-0	34-49-11	D10849	DED			D40680J	12			YC053-YN236, YN501-YR328
2003B	24	Y2	GC		1-3	34-49-11	D40680J	17			D40147J	22			YC053-YN236, YN501-YR328
2003R	24	Y2	GC		0-0	34-49-11	D40680J	18			D40147J	21			YC053-YN236, YN501-YR328
2003Z			GC		0-0	34-49-11	D40680J	16			D40147J	20			YC053-YN236, YN501-YR328
2004B	24	7K	GD		1-6	34-49-11	D40680J	21			D40668J	29			YC053-YD157
2004B	24	7K	GD		1-5	34-49-11	D40680J	21			D40668J	29			YD158-YN236, YN501-YR328
2004W	24	7K	GD		0-0	34-49-11	D40680J	20			D40668J	30			YC053-YN236, YN501-YR328
2004Z			GD		0-0	34-49-11	D40680J	19			D40668J	28			YC053-YN236, YN501-YR328
2601B	24	7K	SA		1-7	34-41-11	D40668J	24			D40147J	7			YC053-YD157
2601B	24	7K	SA		1-8	34-41-11	D40668J	24			D40147J	7			YD158-YN236, YN501-YR328
2601W	24	7K	SA		0-0	34-41-11	D40668J	23			D40147J	6			YC053-YN236, YN501-YR328
2601Z			SA		0-0	34-41-11	D40668J	22			D40147J	5			YC053-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0070

Page 26

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0076	286A0076				J22 JUNCTION BOX (CONTAINS ENGINE 1 WIRING) (continued)										
2602B	24	7K	SB		1-7	34-41-11	D40147J	16			D40668J	27			YC053-YD157
2602B	24	7K	SB		1-8	34-41-11	D40147J	16			D40668J	27			YD158-YN236, YN501-YR328
2602W	24	7K	SB		0-0	34-41-11	D40147J	15			D40668J	26			YC053-YN236, YN501-YR328
2602Z			SB		0-0	34-41-11	D40147J	14			D40668J	25			YC053-YN236, YN501-YR328
2603B	24	7K	SC		2-7	34-41-11	D40147J	19			D10849	5			YC053-YD157
2603B	24	7K	SC		2-8	34-41-11	D40147J	19			D10849	5			YD158-YN236, YN501-YR328
2603W	24	7K	SC		0-0	34-41-11	D40147J	18			D10849	1			YC053-YN236, YN501-YR328
2603Z			SC		0-0	34-41-11	D40147J	17			D10849	DED			YC053-YN236, YN501-YR328
2604B	24	7K	SD		2-7	34-41-11	D10849	3			D40147J	12			YC053-YD157
2604B	24	7K	SD		2-8	34-41-11	D10849	3			D40147J	12			YD158-YN236, YN501-YR328
2604W	24	7K	SD		0-0	34-41-11	D10849	13			D40147J	9			YC053-YN236, YN501-YR328
2604Z			SD		0-0	34-41-11	D10849	DED			D40147J	8			YC053-YN236, YN501-YR328
W0078	286A0078				J23 (J-BOX)										
0001	22	PA			1-5	35-21-11	D02884	D2			TB0023Y	B001	1A		YC051-YC058
0001	22	PA			2-11	35-21-11	D02884	D2			TB0023Y	B001	1A		YC059-YR328
0002	22	PA			2-5	35-21-11	D40686J	13			TB0023Y	B001	1A		YC051-YC058
0002	22	PA			2-7	35-21-11	D40686J	13			TB0023Y	B001	1A		YC059-YR328
0099	20	PA			1-5	73-21-11	D10920			FA	GB00023	ST..	1A		YC056-YC058
0099	20	PA			1-6	73-21-11	D10920			FA	GB00023	ST..	1A		YC059-YR328
0231	22	PA			2-5	23-31-06	D40686J	3			TB0023Y	B001	1A		YC051-YC058
0231	22	PA			2-7	23-31-06	D40686J	3			TB0023Y	B001	1A		YC059-YN260
0231	22	PA			2-7	44-21-22	D40686J	3			TB0023Y	B001	1A		YN501-YR328
0301	22	PA			2-7	35-21-11	D40688J	1			D02882	X1			YC051-YC058
0301	22	PA			2-6	35-21-11	D40688J	1			D02882	X1			YC059-YR328
0302	16	PA			2-9	35-21-11	D40688J	2			TB0023V	B007	1		YC051-YC058
0302	16	PA			3-0	35-21-11	D40688J	2			TB0023V	B007	1		YC059-YR328
0303	16	PA			2-9	35-21-11	D40688J	3			TB0023V	A007	1		YC051-YC058
0303	16	PA			3-0	35-21-11	D40688J	3			TB0023V	A007	1		YC059-YR328
0304	16	PA			2-9	35-21-11	D40688J	4			TB0023V	B005	1		YC051-YC058

WIRE LIST

D280A108

91-21-11

Section W0070

Page 27

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0078		286A0078			J23 (J-BOX) (continued)											
0304		16		PA		3-0	35-21-11	D40688J		4		TB0023V	B005	1		YC059-YR328
0305		16		PA		2-9	35-21-11	D40688J		5		TB0023V	A005	1		YC051-YC058
0305		16		PA		3-0	35-21-11	D40688J		5		TB0023V	A005	1		YC059-YR328
0306		22		PA		2-7	35-21-11	D40688J		6		D02882	X2			YC051-YC058
0306		22		PA		2-6	35-21-11	D40688J		6		D02882	X2			YC059-YR328
0307		16		PA		1-6	35-21-11	D02880		A2		TB0023V	A007	1		YC051-YC058
0307		16		PA		2-8	35-21-11	D02880		A2		TB0023V	A007	1		YC059-YR328
0308		16		PA		1-6	35-21-11	D02880		B2		TB0023V	B007	1		YC051-YC058
0308		16		PA		2-8	35-21-11	D02880		B2		TB0023V	B007	1		YC059-YR328
0309		22		PA		1-7	35-21-11	D02880		C2		TB0023Y	A009	1A		YC051-YC058
0309		22		PA		2-8	35-21-11	D02880		C2		TB0023Y	A009	1A		YC059-YR328
0310		22		PA		1-7	35-21-11	D02880		X1		TB0023Y	B009	1A		YC051-YC058
0310		22		PA		2-8	35-21-11	D02880		X1		TB0023Y	B009	1A		YC059-YR328
0311		22		PA		2-5	35-21-11	D40686J		12		TB0023Y	A009	1A		YC051-YC058
0311		22		PA		2-6	35-21-11	D40686J		12		TB0023Y	A009	1A		YC059-YR328
0312		22		PA		0-7	35-21-11	TB0023Y	A009	1A		TB0023Y	B009	1A		ALL
0313		22		PA		1-10	35-21-11	D02880		X2		D02886	1			YC051-YC058
0313		22		PA		1-9	35-21-11	D02880		X2		D02886	1			YC059-YR328
0314		16		PA		1-6	35-21-11	D02880		A1		TB0023V	A005	1		YC051-YC058
0314		16		PA		2-8	35-21-11	D02880		A1		TB0023V	A005	1		YC059-YR328
0315		16		PA		1-6	35-21-11	D02880		B1		TB0023V	B005	1		YC051-YC058
0315		16		PA		2-8	35-21-11	D02880		B1		TB0023V	B005	1		YC059-YR328
0316		22		PA		1-7	35-21-11	D02880		C1		TB0023Y	A003	1A		YC051-YC058
0316		22		PA		1-4	35-21-11	D02880		C1		TB0033Z	A013	1A		YC059-YR328
0317		20		PA		1-4	35-21-11	D02886		2		GD00526	DC..	1		YC051-YC058
0317		20		PA		1-3	35-21-11	D02886		2		GD00526	DC..	1		YC059-YR328
0318		22		PA		1-6	35-21-11	D02882		C2		TB0023Y	B009	1A		YC051-YC058
0318		22		PA		2-9	35-21-11	D02882		C2		TB0023Y	B009	1A		YC059-YR328
0319		16		PA		1-5	35-21-11	D02882		B2		TB0023V	B007	1		YC051-YC058
0319		16		PA		2-9	35-21-11	D02882		B2		TB0023V	B007	1		YC059-YR328
0320		16		PA		1-5	35-21-11	D02882		A2		TB0023V	A007	1		YC051-YC058
0320		16		PA		2-9	35-21-11	D02882		A2		TB0023V	A007	1		YC059-YR328
0321		22		PA		1-6	35-21-11	D02882		C1		TB0023Y	A003	1A		YC051-YC058
0321		22		PA		1-5	35-21-11	D02882		C1		TB0033Z	A013	1A		YC059-YR328
0322		16		PA		1-5	35-21-11	D02882		B1		TB0023V	B005	1		YC051-YC058
0322		16		PA		2-9	35-21-11	D02882		B1		TB0023V	B005	1		YC059-YR328
0323		16		PA		1-5	35-21-11	D02882		A1		TB0023V	A005	1		YC051-YC058
0323		16		PA		2-9	35-21-11	D02882		A1		TB0023V	A005	1		YC059-YR328
0324		22		PA		1-5	35-21-11	D02884		A2		TB0023Y	B009	1A		YC051-YC058

WIRE LIST

D280A108

91-21-11

Section W0070

Page 28

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0078	286A0078				J23 (J-BOX) (continued)											
0324	22		PA		2-10	35-21-11		D02884		A2		TB0023Y	B009	1A		YC059-YR328
0325	22		PA		1-5	35-21-11		D02884		B2		TB0023Y	A001	1A		YC051-YC058
0325	22		PA		2-11	35-21-11		D02884		B2		TB0023Y	A001	1A		YC059-YR328
0326	22		PA		1-5	35-21-11		D02884		D1		TB0023Y	A001	1A		YC051-YC058
0326	22		PA		2-11	35-21-11		D02884		D1		TB0023Y	A001	1A		YC059-YR328
0327	20		PA		2-3	35-21-11		TB0023Y	A001	1A		GD00526	DC..	1		ALL
0328	22		PA		1-5	35-21-11		D02884		X2		TB0023Y	A001	1A		YC051-YC058
0328	22		PA		2-11	35-21-11		D02884		X2		TB0023Y	A001	1A		YC059-YR328
0329	22		PA		1-5	35-21-11		D02884		A1		TB0023Y	A003	1A		YC051-YC058
0329	22		PA		1-6	35-21-11		D02884		A1		TB0033Z	A013	1A		YC059-YR328
0330	22		PA		1-5	35-21-11		D02884		X1		TB0023Y	A003	1A		YC051-YC058
0330	22		PA		1-6	35-21-11		D02884		X1		TB0033Z	A013	1A		YC059-YR328
0331	24		PK		2-3	33-25-11		D40686J		4		D02884	B1			YC051-YC058
0331	24		PK		2-2	33-25-11		D40686J		4		D02884	B1			YC059-YR328
0332	18		CQ		2-3	33-25-11		D40686J		1		D02884	C2			ALL
0333	18		CQ		2-3	33-25-11		D40686J		2		D02884	C3			ALL
0507	18		PA		2-10	24-11-11		D40688J		7		D10920	C2			ALL
0508	18		PA		2-10	24-11-11		D40688J		8		D10920	C3			ALL
2607B	24		Y2	SG	2-4	73-21-11		D40686J		6		D10920	A2			ALL
2607R	24		Y2	SG	0-0	73-21-11		D40686J		7		D10920	A1			ALL
2607Z				SG	0-0	73-21-11		D40686J		5		GD00526	ST..	1		YC051-YC052
2607Z				SG	0-0	73-21-11		D40686J		5		GD00536	ST..	1A		YC053-YC055
2607Z				SG	0-0	73-21-11		D40686J		5		D10920			FA	YC056-YR328
6008	24		B6		2-4	76-21-11		D40686J		8		D10920	Y2			ALL
6009	24		B6		2-4	76-21-11		D40686J		9		D10920	X2			ALL
6010	24		B6		2-5	76-21-11		D40686J		10		TB0023Y	A011	1A		YC051-YC058
6010	24		B6		2-6	76-21-11		D40686J		10		TB0023Y	A011	1A		YC059-YR328
6050	24		B6		1-4	76-21-11		D10920		X1		TB0023Y	A011	1A		YC051-YC058
6050	24		B6		1-3	76-21-11		D10920		X1		TB0023Y	A011	1A		YC059-YR328
6051	24		B6		1-4	76-21-11		D10920		Y1		TB0023Y	A011	1A		YC051-YC058
6051	24		B6		1-3	76-21-11		D10920		Y1		TB0023Y	A011	1A		YC059-YR328

WIRE LIST

D280A108

91-21-11

Section W0070

Page 29 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice		
W0080	286A0080				J24 BOX											
0001	20		PA		1-2	52-71-14	D12758		A2			SM00003		9	YC051-YD158	
0001	20		PA		0-9	52-71-14	D12758		A2			SM00003		9	YL951-YR328	
0002	20		PA		0-11	52-71-14	D40702J		20			SM00003		9	ALL	
0003	20		PA		1-2	52-71-14	D12758		X1			SM00003		9	YC051-YD158	
0003	20		PA		0-9	52-71-14	D12758		X1			SM00003		9	YL951-YR328	
0004	20		PA		1-4	52-71-14	D12758		X2			D40700J	22		YC051-YD158	
0004	20		PA		1-0	52-71-14	D12758		X2			D40700J	22		YL951-YR328	
0005	20		PA		2-8	52-71-14	D12758		A1			TB0034Y	B007	1A	YC051-YD158	
0005	20		PA		2-6	52-71-14	D12758		A1			TB0034Y	B007	1A	YL951-YR328	
0006	20		PA		1-0	52-71-14	D12540		B1			SM00010		9	YC051-YD158	
0006	20		PA		0-9	52-71-14	D12540		B1			SM00010		9	YL951-YL999, YR301-YR328	
0006	20		PA		2-5	52-71-14	D12540		B1			TB0034Y	A007	1A	YN231-YN236, YN501	
0007	20		PA		1-3	52-71-14	D12540		A1			D40700J	25		YC051-YD158	
0007	20		PA		1-0	52-71-14	D12540		A1			D40700J	25		YL951-YR328	
0008	20		PA		2-9	52-71-14	D12540		B2			GD00534	DC..	1A	YC051-YD158	
0008	20		PA		2-8	52-71-14	D12540		B2			GD00534	DC..	1A	YL951-YR328	
0009	20		PA		2-9	52-71-14	D12540		A2			GD00534	DC..	1A	YC051-YD158	
0009	20		PA		2-8	52-71-14	D12540		A2			GD00534	DC..	1A	YL951-YR328	
0010	20		PA		2-0	52-71-14	D10916		A1			D40700J	26		YC051-YD158	
0010	20		PA		2-1	52-71-14	D10916		A1			D40700J	26		YL951-YR328	
0011	24		PK		1-10	73-22-31	D12540		X1			TB0024Y	A001	1A	YC051-YD158, YL951-YN235, YN237-YN260	
0011	24		PK		1-9	73-22-31	D12540		X1			TB0024Y	A001	1A	YN236	
0011	24		PK		0-9	73-22-31	D12540		X1			SM00016		9	YN501-YR328	
0012	24		PK		1-0	73-22-31	D12540		X2			SM00005		9	YC051-YD158	
0012	24		PK		0-9	73-22-31	D12540		X2			SM00005		9	YL951-YR328	
0013	24		PK		1-9	73-22-31	D10916		X2			SM00005		9	YC051-YD158	
0013	24		PK		1-10	73-22-31	D10916		X2			SM00005		9	YL951-YR328	
0014	20		PA		1-2	52-71-14	D12758		B2			SM00003		9	YC051-YD158	
0014	20		PA		0-9	52-71-14	D12758		B2			SM00003		9	YL951-YL999, YR301-YR328	
0015	20		PA		1-11	52-71-14	D12758		B1			TB0024Y	B003	1A	YC051-YD158	
0015	20		PA		1-10	52-71-14	D12758		B1			TB0024Y	B003	1A	YL951-YL999	
0015	20		PA		1-9	52-71-14	D12758		B1			TB0024Y	B003	1A	YR301-YR314	
0015	20		PA		1-8	52-71-14	D12758		B1			TB0024Y	B003	1A	YR315-YR328	
0016	20		PA		2-4	52-71-14	TB0034Y		B007	1A		D40700J	23		YC051-YD158	
0016	20		PA		2-6	52-71-14	D40700J		23			TB0034Y	B007	1A	YL951-YR328	

WIRE LIST

D280A108

91-21-11

Section W0080

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0080	286A0080				J24 BOX (continued)										
0017	20		PA		0-10	52-71-14	SM00010		9		D40700J	24			YC051-YD158
0017	20		PA		0-9	52-71-14	D40700J		24		SM00010		9		YL951-YL999, YR301-YR328
0017	20		PA		2-6	52-71-14	D40700J		24		TB0034Y	A007	1A		YN231-YN501
0018	20		PA		1-10	52-71-14	TB0034Y	A007	1A		TB0024Y	A003	1A		YC051-YD170
0018	20		PA		1-11	52-71-14	TB0024Y	A003	1A		TB0034Y	A007	1A		YL951-YL999
0018	20		PA		1-10	52-71-14	TB0024Y	A003	1A		TB0034Y	A007	1A		YR301-YR314
0018	20		PA		1-8	52-71-14	TB0024Y	A003	1A		TB0034Y	A007	1A		YR315-YR328
0021	20		PA		1-8	52-71-14	TB0024Y	B003	1A		D40700J	27			YC051-YD158
0021	20		PA		1-10	52-71-14	D40700J		27		TB0024Y	B003	1A		YL951-YL999
0021	20		PA		1-9	52-71-14	D40700J		27		TB0024Y	B003	1A		YR301-YR314
0021	20		PA		1-8	52-71-14	D40700J		27		TB0024Y	B003	1A		YR315-YR328
0023	22		PA		1-4	23-71-01	D12540		C1		D40698J	2			ALL
0024	20		PA		2-9	23-71-01	D12540		C2		GD00534	DC..	1A		YC051-YD158
0024	20		PA		2-8	23-71-01	D12540		C2		GD00534	DC..	1A		YL951-YR328
0025	22		PA		2-0	23-71-01	D12540		C3		D40698J	5			YC051-YC052
0025	22		PA		1-4	23-71-01	D12540		C3		D40698J	5			YC053-YR328
0028	24		PK		0-11	73-22-31	D13132		X1		SM00016		9		YN501-YR328
0029	24		PK		0-11	73-22-31	D13132		X2		SM00005		9		YN501-YR328
0050	20		PA		2-0	52-71-14	TB0034Y	A007	1A		SM00010		9		YC051-YD158
0050	20		PA		2-3	52-71-14	TB0034Y	A007	1A		SM00010		9		YL951-YL999, YR301-YR328
0501	22		PA		2-1	27-62-11	D40694J		26		D11402	13			YC051-YD158
0501	22		PA		2-3	27-62-11	D40694J		26		D11402	13			YL951-YR328
0502	20		PA		2-0	27-62-11	D11402		1		GD00524	DC..	1A		YC051-YD158
0502	20		PA		2-3	27-62-11	D11402		1		GD00524	DC..	1A		YL951-YR328
0504	22		PA		1-9	29-23-11	D40698J		7		D40694J	8			YC051-YD158
0504	22		PA		1-8	29-23-11	D40698J		7		D40694J	8			YL951-YR328
0505	22		CQ		1-5	32-31-12	D40700J		3		D40698J	1			ALL
0506	22		G5		1-7	32-31-12	D40702J		9		D40698J	11			ALL
0507	22		G5		1-7	32-31-12	D40702J		10		D40698J	12			ALL
0508	22		G5		1-7	32-31-12	D40702J		11		D40698J	13			ALL
0509	22		G5		2-1	32-31-12	D40698J		10		TB0024Y	B005	1A		YC051-YD158, YN236, YN501-YR314
0509	22		G5		2-2	32-31-12	D40698J		10		TB0024Y	B005	1A		YL951-YN235, YN237-YN260
0509	22		G5		2-0	32-31-12	D40698J		10		TB0024Y	B005	1A		YR315-YR328
0510	22		G5		1-7	32-31-12	D40702J		12		D40698J	14			ALL

WIRE LIST

D280A108

91-21-11

Section W0080

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0080	286A0080			J24 BOX (continued)											
0511	22		G5		1-4	32-31-12	D11004		X1		TB0024Y	B005	1A		YC051-YN235, YN237-YN260
0511	22		G5		1-3	32-31-12	D11004		X1		TB0024Y	B005	1A		YN236, YN501-YR314
0511	22		G5		1-2	32-31-12	D11004		X1		TB0024Y	B005	1A		YR315-YR328
0512	22		CQ		1-9	32-31-12	D40700J		4		D11004		X2		YC051-YD158
0512	22		CQ		2-0	32-31-12	D40700J		4		D11004		X2		YL951-YR328
0513	22		G5		1-7	32-31-12	D40702J		24		TB0024Y	B005	1A		YC051-YD158, YN236, YN501-YR314
0513	22		G5		1-8	32-31-12	D40702J		24		TB0024Y	B005	1A		YL951-YN235, YN237-YN260
0513	22		G5		1-6	32-31-12	D40702J		24		TB0024Y	B005	1A		YR315-YR328
0515	20		PA		2-0	32-41-11	D11402		3		GD00524	DC..	1A		YC051-YD158
0515	20		PA		2-3	32-41-11	D11402		3		GD00524	DC..	1A		YL951-YR328
0516	22		PA		2-9	32-41-11	D40698J		9		D11402		5		YC051-YD158
0516	22		PA		2-11	32-41-11	D40698J		9		D11402		5		YL951-YR328
0517	22		G5		2-3	32-41-11	D40702J		5		D11402		12		YC051-YD158
0517	22		G5		2-5	32-41-11	D40702J		5		D11402		12		YL951-YR328
0518	22		G5		2-3	32-41-11	D40702J		6		D11402		6		YC051-YD158
0518	22		G5		2-5	32-41-11	D40702J		6		D11402		6		YL951-YR328
0519	22		PA		2-4	32-44-11	D40702J		1		D11154		3		YC051-YD158
0519	22		PA		2-5	32-44-11	D40702J		1		D11154		3		YL951-YR328
0520	22		PA		2-4	32-44-11	D40702J		2		D11154		4		YC051-YD158
0520	22		PA		2-5	32-44-11	D40702J		2		D11154		4		YL951-YR328
0521	22		PA		2-4	32-44-11	D40702J		3		D11154		12		YC051-YD158
0521	22		PA		2-5	32-44-11	D40702J		3		D11154		12		YL951-YR328
0522	20		PA		2-1	32-44-11	D11154		6		GD00524	DC..	1A		YC051-YD158
0522	20		PA		2-3	32-44-11	D11154		6		GD00524	DC..	1A		YL951-YR328
0523	22		PA		2-4	32-44-11	D40702J		4		D11154		5		YC051-YD158
0523	22		PA		2-5	32-44-11	D40702J		4		D11154		5		YL951-YR328
1301	20		X1	EN	2-9	73-22-11	D40696J		3		D10952		A1		YC051-YD158
1301	20		X1	EN	3-1	73-22-11	D40696J		3		D10952		A1		YL951-YR328
1301Z				EN	0-0	73-22-11	D40696J		10		GB00034	ST..	1A		ALL
1302	20		X1	EP	1-11	73-22-11	D40694J		11		D10952		B1		YC051-YD158
1302	20		X1	EP	2-3	73-22-11	D40694J		11		D10952		B1		YL951-YR328
1302Z				EP	0-0	73-22-11	D40694J		23		GB00034	ST..	1A		ALL
2601B	24		Y2	SA	2-5	73-21-11	D40696J		2		D10926		A2		ALL
2601R	24		Y2	SA	0-0	73-21-11	D40696J		1		D10926		A1		ALL
2601Z				SA	0-0	73-21-11	D40696J		9		GD00524	ST..	1A		ALL
2602B	24		7K	SB	2-9	34-41-11	D40698J		17		D10847		3		YC053-YD158

WIRE LIST

D280A108

91-21-11

Section W0080

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0080	286A0080			J24 BOX (continued)											
2602B	24		7K	SB	2-10	34-41-11	D40698J		17		D10847		3		YL951-YR328
2602W	24		7K	SB	0-0	34-41-11	D40698J		16		D10847		13		YC053-YR328
2602Z				SB	0-0	34-41-11	D40698J		22		D10847		DED		YC053-YR328
2603B	24		7K	SC	2-9	34-41-11	D40698J		19		D10847		5		YC053-YD158
2603B	24		7K	SC	2-10	34-41-11	D40698J		19		D10847		5		YL951-YR328
2603W	24		7K	SC	0-0	34-41-11	D40698J		18		D10847		1		YC053-YR328
2603Z				SC	0-0	34-41-11	D40698J		23		D10847		DED		YC053-YR328
2604B	24		7K	SD	2-9	34-49-11	D40698J		28		D10847		4		YC053-YD158
2604B	24		7K	SD	2-10	34-49-11	D40698J		28		D10847		4		YL951-YR328
2604W	24		7K	SD	0-0	34-49-11	D40698J		27		D10847		2		YC053-YR328
2604Z				SD	0-0	34-49-11	D40698J		29		D10847		DED		YC053-YR328
5501	22		PA		1-3	21-25-11	D11874		A1		D40694J		15		YC051-YC059, YC065-YD158
5501	22		PA		1-3	21-25-11	D11874		A1		D12225		5		YC060-YC064
5501	22		PA		2-5	21-25-11	D11874		A1		D12225		5		YL951-YR328
5502	22		PA		2-1	21-25-11	D11874		A2		D11866		8		YC051-YC059, YC065-YD158
5502	22		PA		2-1	21-25-11	D11874		A2		D11866		9		YC060-YC064
5502	22		PA		2-6	21-25-11	D11874		A2		D11866		9		YL951-YR328
5503	22		PA		1-11	21-25-11	D11866		6		D40694J		14		YC051-YC059, YC065-YD158
5503	22		PA		1-11	21-25-11	D11866		11		D40694J		14		YC060-YC064
5503	22		PA		2-3	21-25-11	D11866		11		D40694J		14		YL951-YR328
5504	20		PA		1-5	21-25-11	D11866		3		GD00544		DC..	1	YC051-YC059, YC065-YD158
5504	20		PA		1-5	21-25-11	D11866		12		GD00544		DC..	1	YC060-YC064
5504	20		PA		1-8	21-25-11	D11866		12		GD00544		DC..	1	YL951-YR328
5508	24		PK		2-10	21-27-21	TB0034Y		A005	1A	D40696J		11		YC051-YC059, YC065-YD158
5508	24		PK		2-10	21-27-21	D12229		D3		D40696J		11		YC060-YC064
5508	24		PK		2-2	21-27-21	D12229		D3		D40696J		11		YL951-YR328
5510	22		G5		2-0	21-27-21	TB0034Y		B001	1A	D40694J		18		YC051-YC059, YC065-YD158
5510	22		G5		2-0	21-27-21	D12229		A3		D40694J		18		YC060-YC064
5510	22		G5		1-4	21-27-21	D12229		A3		D40694J		18		YL951-YR328
5513	24		B6		2-5	21-43-21	D11866		7		D40692J		12		YC051-YC059, YC065-YD158
5513	24		B6		2-5	21-43-21	D11866		6		D40692J		12		YC060-YC064
5513	24		B6		2-10	21-43-21	D11866		6		D40692J		12		YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0080

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0080	286A0080				J24 BOX (continued)										
5515	24		B6		0-7	21-43-21	D11874		C2		D11874		D2	*	YC051-YC059, YC065-YD158
5515	24		B6		0-7	21-43-21	D11874		C2		TB0024Z	A021	1A		YC060-YC064
5515	24		B6		1-11	21-43-21	D11874		C2		TB0024Z	A021	1A		YL951-YR328
5516	24		B6		1-6	21-43-21	D11874		D2	*	D40692J		11		YC051-YC059, YC065-YD158
5516	24		B6		1-6	21-43-21	D11874		D2		D40692J		10		YC060-YC064, YD160-YR328
5517	24		B6		1-6	21-43-21	D11874		X1		D40692J		10		YC051-YC059, YC065-YD158
5518	22		CQ		2-0	21-43-21	D11874		X2		GD00544	DC..	1		YC051-YD158
5518	22		CQ		2-2	21-43-21	D11874		X2		GD00544	DC..	1		YL951-YN236, YN501-YR314
5518	22		CQ		2-1	21-43-21	D11874		X2		GD00544	DC..	1		YR315-YR328
5519	24		B6		0-7	21-43-21	D11878		A2		D11878		X1	*	YC051-YC059, YC065-YD158
5520	24		B6		1-7	21-43-21	D11878		X1	*	D11876		X1	*	YC051-YC059, YC065-YD158
5520	24		B6		1-7	21-43-21	D11878		X1		TB0034Y	B015	1A		YC060-YC064
5520	24		B6		1-5	21-43-21	D11878		X1		TB0034Y	B015	1A		YL951-YR328
5521	22		CQ		1-3	21-43-21	D11878		X2		GD00544	DC..	1		ALL
5522	24		B6		1-9	21-43-21	D11876		X1	*	D40692J		3		YC051-YC059, YC065-YD158
5523	24		B6		1-9	21-43-21	D11876		C1		D40692J		1		YC051-YD158
5523	24		B6		2-0	21-43-21	D11876		C1		D40692J		1		YL951-YR328
5524	22		CQ		1-8	21-43-21	D11876		X2		GD00544	DC..	1		YC051-YD158
5524	22		CQ		1-7	21-43-21	D11876		X2		GD00544	DC..	1		YL951-YN236, YN501-YR314
5524	22		CQ		1-6	21-43-21	D11876		X2		GD00544	DC..	1		YR315-YR328
5525	24		B6		1-11	21-43-21	D11874		C3		D11878		B2		YC051-YC059, YC065-YD158
5526	24		B6		1-2	21-43-21	D11874		C1	*	D40702J		16		YC051-YC059, YC065-YD158
5526	24		B6		1-2	21-43-21	D11874		C1		D11866		7		YC060-YC064
5526	24		B6		2-6	21-43-21	D11874		C1		D11866		7		YL951-YR328
5527	24		B6		1-5	21-43-21	D11874		C1	*	D11876		A3		YC051-YC059, YC065-YD158
5528	24		B6		1-11	21-43-21	D11878		B3	*	D40702J		17		YC051-YC059, YC065-YD158

WIRE LIST

D280A108

91-21-11

Section W0080

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0080	286A0080				J24 BOX (continued)										
5528	24		B6		1-11	21-43-21	D11878		B3		D40702J	17			YC060-YC064
5528	24		B6		2-1	21-43-21	D11878		B3		D40702J	17			YL951-YR328
5529	24		B6		1-7	21-43-21	D11878		B3	*	D11876	A1			YC051-YC059, YC065-YD158
5530	24		B6		1-7	21-43-21	D11878		A1		D11876	A2			YC051-YC059, YC065-YD158
5531	24		G6		1-8	21-27-31	D11874		D1		D40698J	15			YC051-YC059, YC065-YD158
5531	24		G6		1-8	21-27-31	TB0034Y	B013	1A		D40698J	15			YC060-YC064
5531	24		G6		2-11	21-27-31	TB0034Y	B013	1A		D40698J	15			YL951-YR328
5532	24		G6		2-0	21-27-21	D40694J		17		TB0034Y	B001	1A		YC051-YD158
5532	24		G6		2-2	21-27-21	D40694J		17		TB0034Y	B001	1A		YL951-YR328
5533	24		PK		0-7	21-27-21	TB0034Y	A001	1A		TB0034Y	A003	1A		ALL
5534	24		PK		1-0	21-27-21	TB0034Y	B003	1A		TB0034Y	B005	1A		YC051-YD158
5534	24		PK		1-1	21-27-21	TB0034Y	B003	1A		TB0034Y	B005	1A		YL951-YR328
5535	24		PK		2-10	21-27-21	D40696J		13		TB0034Y	B005	1A		YC051-YD158
5535	24		PK		3-0	21-27-21	D40696J		13		TB0034Y	B005	1A		YL951-YR328
5536	24		PK		1-1	21-27-21	D12248		2		TB0034Y	A005	1A		YC051-YC059, YC065-YD158
5536	24		PK		1-1	21-27-21	TB0034Y	A013	1A		TB0034Y	A005	1A		YC060-YC064, YD160-YR328
5537	24		PK		2-8	21-27-21	D12248		7		D40696J	15			YC051-YD158
5537	24		PK		3-0	21-27-21	D12248		7		D40696J	15			YL951-YR328
5538	24		PK		1-1	21-27-21	D12248		3		TB0034Y	A003	1A		YC051-YD158
5538	24		PK		1-3	21-27-21	D12248		3		TB0034Y	A003	1A		YL951-YR328
5539	22		PA		1-4	21-27-21	D12248		4		GD00534	DC..	1A		ALL
5551	22		PA		2-0	21-25-11	D12225		3		D12227	5			YC060-YC064
5551	22		PA		1-0	21-25-11	D12225		3		D12227	5			YL951-YR328
5552	20		PA		3-6	21-25-11	D12225		1		GD00544	DC..	1		YC060-YC064
5552	20		PA		1-7	21-25-11	D12225		1		GD00544	DC..	1		YL951-YR328
5553	22		PA		2-0	21-25-11	D12225		2		TB0034Y	A009	1A		YC060-YC064
5553	22		PA		1-3	21-25-11	D12225		2		TB0034Y	A009	1A		YL951-YR328
5554	22		PA		2-0	21-25-11	D12225		12		TB0034Y	A009	1A		YC060-YC064
5554	22		PA		1-3	21-25-11	D12225		12		TB0034Y	A009	1A		YL951-YR328
5555	22		PA		2-0	21-25-11	D12225		6		TB0024Z	A021	1A		YC060-YC064
5555	22		PA		2-2	21-25-11	D12225		6		TB0024Z	A021	1A		YL951-YR328
5556	22		PA		2-2	21-25-11	D12227		3		D40694J	15			YC060-YC064, YD160-YR328
5557	22		PA		3-0	21-25-11	D12227		6		TB0024Z	A021	1A		YC060-YC064

WIRE LIST

D280A108

91-21-11

Section W0080

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To				Effectivity	
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W0080	286A0080			J24 BOX (continued)												
5557	22		PA		2-2	21-25-11	D12227		6		TB0024Z	A021	1A		YL951-YR328	
5558	20		PA		2-6	21-25-11	D12227		1		GD00544	DC..	1		YC060-YC064	
5558	20		PA		1-7	21-25-11	D12227		1		GD00544	DC..	1		YL951-YR328	
5559	22		PA		2-10	21-25-11	D40698J		32		TB0034Y	B009	1A		YC060-YC064, YD160-YR328	
5560	22		PA		2-0	21-25-11	D12227		2		TB0034Y	A011	1A		YC060-YC064	
5560	22		PA		1-3	21-25-11	D12227		2		TB0034Y	A011	1A		YL951-YR328	
5561	22		PA		2-0	21-25-11	D12227		12		TB0034Y	A011	1A		YC060-YC064	
5561	22		PA		1-3	21-25-11	D12227		12		TB0034Y	A011	1A		YL951-YR328	
5562	22		PA		2-10	21-25-11	D40698J		33		TB0034Y	B011	1A		YC060-YC064, YD160-YR328	
5563	24		PK		2-0	21-27-21	D12248		2		TB0034Y	A013	1A		YC060-YC064	
5563	24		PK		1-4	21-27-21	D12248		2		TB0034Y	A013	1A		YL951-YR328	
5564	22		PA		3-0	21-27-21	D12229		D2		TB0034Y	A013	1A		YC060-YC064	
5564	22		PA		1-10	21-27-21	D12229		D2		TB0034Y	A013	1A		YL951-YR328	
5565	22		G5		3-0	21-27-21	D12229		A2		TB0034Y	B001	1A		YC060-YC064	
5565	22		G5		1-9	21-27-21	D12229		A2		TB0034Y	B001	1A		YL951-YR328	
5567	22		G5		2-2	21-27-21	D12229		C1		D40696J		25		YC060-YC064, YD160-YR328	
5568	22		G5		2-2	21-27-21	D12229		C2		D40696J		26		YC060-YC064, YD160-YR328	
5569	22		G5		1-4	21-27-21	D12229		B2		D40694J		19		YC060-YC064, YD160-YR328	
5570	22		G5		1-4	21-27-21	D12229		B3		D40694J		28		YC060-YC064, YD160-YR328	
5571	24		B6		2-3	21-43-21	D40692J		11		TB0024Z	A021	1A		YC060-YC064, YD160-YR328	
5572	24		B6		3-0	21-43-21	D11874		B2		TB0024Z	A021	1A		YC060-YC064	
5572	24		B6		1-11	21-43-21	D11874		B2		TB0024Z	A021	1A		YL951-YR328	
5573	24		B6		2-0	21-43-21	D11874		D1		D11874	X1		*	YC060-YC064	
5573	24		B6		0-7	21-43-21	D11874		D1		D11874	X1		*	YL951-YR328	
5574	24		B6		1-7	21-43-21	D11874		X1	*	D40698J		34		YC060-YC064, YD160-YR328	
5575	24		B6		3-0	21-43-21	D11878		B2		TB0024Z	A021	1A		YC060-YC064	
5575	24		B6		1-10	21-43-21	D11878		B2		TB0024Z	A021	1A		YL951-YR328	
5576	24		B6		2-1	21-43-21	D11878		B1		D40702J		16		YC060-YC064, YD160-YR328	
5577	24		B6		2-0	21-43-21	D11876		A2		D11876	X1		*	YC060-YC064	
5577	24		B6		0-7	21-43-21	D11876		A2		D11876	X1		*	YL951-YR328	

WIRE LIST

D280A108

91-21-11

Section W0080

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0080	286A0080			J24 BOX (continued)											
5578	24	B6		2-1	21-43-21	D11876		X1		*	D40698J	35			YC060-YC064, YD160-YR328
5601	24	B6		2-0	21-43-21	D11866		14			D12225	11			YC060-YC064
5601	24	B6		1-1	21-43-21	D11866		14			D12225	11			YL951-YR328
5602	24	B6		2-0	21-43-21	D11866		4			D12225	7			YC060-YC064
5602	24	B6		1-1	21-43-21	D11866		4			D12225	7			YL951-YR328
5603	24	B6		2-0	21-43-21	D12225		14			D12227	7			YC060-YC064
5603	24	B6		1-0	21-43-21	D12225		14			D12227	7			YL951-YR328
5604	24	B6		3-0	21-43-21	D11866		5			D11874	B1			YC060-YC064
5604	24	B6		2-6	21-43-21	D11866		5			D11874	B1			YL951-YR328
5605	24	B6		2-0	21-43-21	D12225		9			D12227	11			YC060-YC064
5605	24	B6		1-0	21-43-21	D12225		9			D12227	11			YL951-YR328
5606	24	B6		3-0	21-43-21	D12225		8			TB0024Y	A019	1A		YC060-YC064
5606	24	B6		2-1	21-43-21	D12225		8			TB0024Y	A019	1A		YL951-YR328
5607	24	B6		2-0	21-43-21	TB0024Y		B019	1A		TB0024Y	A017	1A		YC060-YC064
5607	24	B6		0-7	21-43-21	TB0024Y		B019	1A		TB0024Y	A017	1A		YL951-YR328
5608	24	B6		2-0	21-43-21	D12227		9			TB0034Y	B013	1A		YC060-YC064
5608	24	B6		1-4	21-43-21	D12227		9			TB0034Y	B013	1A		YL951-YR328
5609	24	B6		3-0	21-43-21	TB0024Y		A017	1A		TB0034Y	B013	1A		YC060-YC064
5609	24	B6		2-1	21-43-21	TB0024Y		A017	1A		TB0034Y	B013	1A		YL951-YR328
5610	24	B6		3-0	21-43-21	TB0024Y		B017	1A		TB0034Y	B015	1A		YC060-YC064
5610	24	B6		2-1	21-43-21	TB0024Y		B017	1A		TB0034Y	B015	1A		YL951-YR328
5611	24	B6		3-0	21-43-21	D11876		A3			TB0034Y	A015	1A		YC060-YC064
5611	24	B6		1-10	21-43-21	D11876		A3			TB0034Y	A015	1A		YL951-YN236, YN501-YR314
5611	24	B6		1-11	21-43-21	D11876		A3			TB0034Y	A015	1A		YR315-YR328
5612	22	G5		2-0	21-27-21	D12229		X1			TB0024Y	A019	1A		YC060-YC064
5612	22	G5		1-3	21-27-21	D12229		X1			TB0024Y	A019	1A		YL951-YN236, YN501-YR314
5612	22	G5		1-2	21-27-21	D12229		X1			TB0024Y	A019	1A		YR315-YR328
5613	20	G5		2-0	21-27-21	D12229		X2			GD00544	DC..	1		YC060-YC064
5613	20	G5		1-6	21-27-21	D12229		X2			GD00544	DC..	1		YL951-YR328
5614	24	B6		2-0	21-43-21	D12227		14			TB0034Y	B013	1A		YC060-YC064
5614	24	B6		1-4	21-43-21	D12227		14			TB0034Y	B013	1A		YL951-YR328
5617	20	PA		1-3	31-35-03	D12540		D2			GD00524	DC..	1A		YN236-YR328
5618	22	PA		1-6	31-35-03	D12540		D1			D40696J	28			YN236-YR328
6001	20	G5		2-3	73-22-11	D40700J		10			D10952	B2			YC051-YD158
6001	20	G5		2-7	73-22-11	D40700J		10			D10952	B2			YL951-YR328
6002	20	PA		2-9	73-22-11	D40696J		4			D10952	A2			YC051-YD158

WIRE LIST

D280A108

91-21-11

Section W0080

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0080	286A0080				J24 BOX (continued)											
6002	20		PA		3-1	73-22-11		D40696J		4		D10952		A2		YL951-YR328
6003	24		PK		1-11	73-22-11		D40694J		9		D10952		X2		YC051-YD158
6003	24		PK		2-3	73-22-11		D40694J		9		D10952		X2		YL951-YR328
6004	24		PK		1-9	73-22-11		D10952		X1		TB0024Y		A001	1A	YC051-YD158
6004	24		PK		2-0	73-22-11		D10952		X1		TB0024Y		A001	1A	YL951-YN235, YN237-YN260
6004	24		PK		1-11	73-22-11		D10952		X1		TB0024Y		A001	1A	YN236
6004	24		PK		2-4	73-22-11		D10952		X1		SM00016			9	YN501-YR328
6005	24		PK		2-2	73-22-31		D40696J		7		TB0024Y		A001	1A	YC051-YD158
6005	24		PK		2-4	73-22-31		D40696J		7		TB0024Y		A001	1A	YL951-YN235, YN237-YN260
6005	24		PK		2-3	73-22-31		D40696J		7		TB0024Y		A001	1A	YN236
6005	24		PK		1-3	73-22-31		D40696J		7		SM00016			9	YN501-YR328
6006	24		PK		1-6	73-22-31		D10916		X1		TB0024Y		A001	1A	YC051-YD158, YL951-YN235, YN237-YN260
6006	24		PK		1-5	73-22-31		D10916		X1		TB0024Y		A001	1A	YN236
6006	24		PK		1-10	73-22-31		D10916		X1		SM00016			9	YN501-YR328
6007	24		PK		1-1	73-22-31		D40694J		12		SM00005			9	ALL
6008	24		PK		1-8	73-22-31		D10916		A2		GD00524		DC..	1A	ALL
6009	24		PK		1-10	73-22-31		D40702J		8		D10916		A3		YC051-YD158
6009	24		PK		1-11	73-22-31		D40702J		8		D10916		A3		YL951-YR328
6010	24		PK		2-2	76-21-21		D40696J		8		TB0024Y		B001	1A	YC051-YD158, YR315-YR328
6010	24		PK		2-4	76-21-21		D40696J		8		TB0024Y		B001	1A	YL951-YN235, YN237-YN260
6010	24		PK		2-3	76-21-21		D40696J		8		TB0024Y		B001	1A	YN236, YN501-YR314
6011	24		PK		1-5	76-21-21		D10926		X1		TB0024Y		B001	1A	YC051-YD158, YL951-YN235, YN237-YN260
6011	24		PK		1-3	76-21-21		D10926		X1		TB0024Y		B001	1A	YN236, YN501-YR328
6012	24		PK		1-5	76-21-21		D10926		Y1		TB0024Y		B001	1A	YC051-YD158, YL951-YN235, YN237-YN260
6012	24		PK		1-3	76-21-21		D10926		Y1		TB0024Y		B001	1A	YN236, YN501-YR328
6013	24		PK		2-5	76-21-21		D40696J		5		D10926		Y2		ALL
6014	20		PA		1-6	76-21-21		D10926		C3		GD00524		DC..	1A	YC051-YD158
6014	20		PA		1-7	76-21-21		D10926		C3		GD00524		DC..	1A	YL951-YR328
6015	24		PK		2-5	76-21-21		D40696J		6		D10926		X2		ALL

WIRE LIST

D280A108

91-21-11

Section W0080

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0080	286A0080				J24 BOX (continued)										
6016	24		PK		1-7	76-21-21	D40694J		7		D10926		C2		ALL
6017	18		CQ		1-0	78-32-61	D40692J		13		SM00004			9	YC051-YL999, YR301-YR328
6017	18		CQ		2-1	78-32-61	D40692J		13		TB0024Y	A003	1D		YN231-YN235, YN237-YN260
6017	18		CQ		2-0	78-32-61	D40692J		13		TB0024Y	A003	1D		YN236, YN501
6018	18		CQ		1-10	78-32-61	D10638		B1		SM00004			9	YC051-YD158
6018	18		CQ		2-1	78-32-61	D10638		B1		SM00004			9	YL951-YL999, YR301-YR328
6018	18		CQ		1-10	78-32-61	D10638		B1		TB0024Y	A003	1D		YN231-YN235, YN237-YN260
6018	18		CQ		1-9	78-32-61	D10638		B1		TB0024Y	A003	1D		YN236, YN501
6019	18		CQ		1-10	78-32-61	D10638		A1		SM00004			9	YC051-YD158
6019	18		CQ		2-1	78-32-61	D10638		A1		SM00004			9	YL951-YL999, YR301-YR328
6019	18		CQ		1-10	78-32-61	D10638		A1		TB0024Y	A003	1D		YN231-YN235, YN237-YN260
6019	18		CQ		1-9	78-32-61	D10638		A1		TB0024Y	A003	1D		YN236, YN501
6020	22		CQ		1-8	78-32-61	D10640		A2		GD00534	DC..	1A		YC051-YD158
6020	22		CQ		1-6	78-32-61	D10640		A2		GD00534	DC..	1A		YL951-YR328
6021	22		CQ		1-8	78-32-61	D10640		X2		GD00534	DC..	1A		YC051-YD158
6021	22		CQ		1-6	78-32-61	D10640		X2		GD00534	DC..	1A		YL951-YR328
6022	22		CQ		1-3	78-32-61	D10640		A1		D10638		Y2		YC051-YD158
6022	22		CQ		1-2	78-32-61	D10640		A1		D10638		Y2		YL951-YR328
6023	18		CQ		1-5	78-32-61	D10638		A3		GD00534	DC..	1D		YC051-YD158
6023	18		CQ		1-4	78-32-61	D10638		A3		GD00534	DC..	1D		YL951-YR328
6024	18		CQ		1-5	78-32-61	D10638		B3		GD00534	DC..	1D		YC051-YD158
6024	18		CQ		1-4	78-32-61	D10638		B3		GD00534	DC..	1D		YL951-YR328
6025	22		CQ		1-5	78-32-61	D10638		X2		GD00534	DC..	1A		YC051-YD158
6025	22		CQ		1-4	78-32-61	D10638		X2		GD00534	DC..	1A		YL951-YR328
6026	18		CQ		2-3	78-32-61	TB0024Y		A009	1D	GD00534	DC..	1D		YC051-YD158
6026	18		CQ		2-2	78-32-61	TB0024Y		A009	1D	GD00534	DC..	1D		YL951-YN235, YN237-YN260, YR315-YR328
6026	18		CQ		2-1	78-32-61	TB0024Y		A009	1D	GD00534	DC..	1D		YN236, YN501-YR314
6027	22		CQ		1-1	78-32-61	D03529		X2		M01667		A	C	YC051-YD158
6027	22		CQ		2-8	78-32-61	D03529		X2		M01667		A	C	YL951-YR328
6028	22		CQ		1-4	78-32-61	M01667		B	C	GD00534	DC..	1A		ALL
6029	18		CQ		2-3	78-32-61	TB0024Y		A011	1D	GD00534	DC..	1D		YC051-YD158

WIRE LIST

D280A108

91-21-11

Section W0080

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W0080	286A0080	J24 BOX (continued)			
6029	18 CQ	2-2 78-32-61	TB0024Y A011 1D	GD00534 DC.. 1D	YL951-YN235, YN237-YN260, YR315-YR328
6029	18 CQ	2-1 78-32-61	TB0024Y A011 1D	GD00534 DC.. 1D	YN236, YN501-YR314
6030	20 PA	2-0 78-34-21	SM00015 9	D03529 A1	YC051-YD158
6030	20 PA	1-0 78-34-21	SM00015 9	D03529 A1	YL951-YR328
6031	20 PA	1-11 78-34-21	D03529 A2	TB0024Y B007 1A	YC051-YD158
6031	20 PA	1-0 78-34-21	D03529 A2	SM00028 9	YL951-YR328
6032	20 PA	1-4 78-34-21	D11004 A3	GD00524 DC.. 1A	YC051-YD158
6032	20 PA	1-7 78-34-21	D11004 A3	GD00524 DC.. 1A	YL951-YR328
6033	20 PA	1-4 78-34-21	D11004 A2	TB0024Y B007 1A	YC051-YD158
6033	20 PA	1-9 78-34-21	D11004 A2	SM00028 9	YL951-YR328
6034	20 PA	1-7 78-34-21	D40702J 7	TB0024Y B007 1A	YC051-YD158
6034	20 PA	0-11 78-34-21	D40702J 7	SM00028 9	YL951-YR328
6035	22 CQ	1-11 78-32-61	D03529 X1	TB0024Y A005 1A	YC051-YD158, YN236, YN501-YR314
6035	22 CQ	2-0 78-32-61	D03529 X1	TB0024Y A005 1A	YL951-YN235, YN237-YN260
6035	22 CQ	1-10 78-32-61	D03529 X1	TB0024Y A005 1A	YR315-YR328
6036	22 CQ	1-10 78-32-61	D10640 X1	SM00006 9	YC051-YD158
6036	22 CQ	1-7 78-32-61	D10640 X1	TB0024Y A007 1A	YL951-YN235, YN237-YN260
6036	22 CQ	1-6 78-32-61	D10640 X1	TB0024Y A007 1A	YN236, YN501-YR314
6036	22 CQ	1-5 78-32-61	D10640 X1	TB0024Y A007 1A	YR315-YR328
6037	22 CQ	2-2 78-32-61	D40700J 7	D10638 X1	YC051-YD158
6037	22 CQ	2-4 78-32-61	D40700J 7	D10638 X1	YL951-YR328
6038	22 CQ	1-10 78-32-61	D10638 Y1	SM00006 9	YC051-YD158
6038	22 CQ	1-9 78-32-61	D10638 Y1	TB0024Y A007 1A	YL951-YN235, YN237-YN260
6038	22 CQ	1-8 78-32-61	D10638 Y1	TB0024Y A007 1A	YN236, YN501-YR328
6039	22 CQ	0-10 78-32-61	D40700J 5	SM00006 9	YC051-YD158
6039	22 CQ	1-10 78-32-61	D40700J 5	TB0024Y A007 1A	YL951-YN235, YN237-YN260
6039	22 CQ	1-9 78-32-61	D40700J 5	TB0024Y A007 1A	YN236, YN501-YR314
6039	22 CQ	1-8 78-32-61	D40700J 5	TB0024Y A007 1A	YR315-YR328
6040	18 CQ	1-8 78-32-61	D10638 A2	TB0024Y A005 1D	YC051-YD158, YN236, YN501-YR314
6040	18 CQ	1-9 78-32-61	D10638 A2	TB0024Y A005 1D	YL951-YN235, YN237-YN260

WIRE LIST

D280A108

91-21-11

Section W0080

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0080	286A0080				J24 BOX (continued)										
6040	18		CQ		1-7	78-32-61	D10638	A2			TB0024Y	A005	1D		YR315-YR328
6041	18		CQ		0-11	78-32-61	TB0024Y	A005	1D		TB0024Y	B009	1D		YC051-YD158, YN236, YN501-YR314
6041	18		CQ		1-0	78-32-61	TB0024Y	A005	1D		TB0024Y	B009	1D		YL951-YN235, YN237-YN260
6041	18		CQ		0-10	78-32-61	TB0024Y	A005	1D		TB0024Y	B009	1D		YR315-YR328
6042	18		CQ		2-0	78-32-61	D40692J	6			TB0024Y	B009	1D		YC051-YD158, YN236-YR328
6042	18		CQ		2-1	78-32-61	D40692J	6			TB0024Y	B009	1D		YL951-YN235
6043	18		CQ		2-9	78-32-61	D40692J	5			GD00534	DC..	1D		YC051-YD158
6043	18		CQ		3-0	78-32-61	D40692J	5			GD00534	DC..	1D		YL951-YR328
6044	22		CQ		1-9	78-32-61	D40700J	17			TB0024Y	A005	1A		YC051-YD158, YN236, YN501-YR314
6044	22		CQ		1-10	78-32-61	D40700J	17			TB0024Y	A005	1A		YL951-YN235, YN237-YN260
6044	22		CQ		1-8	78-32-61	D40700J	17			TB0024Y	A005	1A		YR315-YR328
6045	22		CQ		1-9	78-32-61	D40700J	9			TB0024Y	A007	1A		YC051-YD158
6045	22		CQ		0-9	78-32-61	D40700J	9			SM00026		9		YL951-YR328
6046	18		CQ		1-8	78-32-61	D10638	B2			TB0024Y	A007	1D		YC051-YD158
6046	18		CQ		2-1	78-32-61	D10638	B2			SM00026		9		YL951-YR328
6047	18		CQ		0-11	78-32-61	TB0024Y	A007	1D		TB0024Y	B011	1D		YC051-YD158
6047	18		CQ		1-7	78-32-61	SM00026		9		TB0024Y	B011	1D		YL951-YN235, YN237-YN260, YR315-YR328
6047	18		CQ		1-6	78-32-61	SM00026		9		TB0024Y	B011	1D		YN236, YN501-YR314
6048	18		CQ		2-0	78-32-61	D40692J	8			TB0024Y	B011	1D		YC051-YD158, YN236-YR328
6048	18		CQ		2-1	78-32-61	D40692J	8			TB0024Y	B011	1D		YL951-YN235
6049	18		CQ		2-9	78-32-61	D40692J	7			GD00534	DC..	1D		YC051-YD158
6049	18		CQ		3-0	78-32-61	D40692J	7			GD00534	DC..	1D		YL951-YR328
6050	20		PA		1-9	78-34-21	D40700J	6			TB0024Y	B007	1A		YC051-YD158
6050	20		PA		0-9	78-34-21	D40700J	6			SM00028		9		YL951-YR328
6051	20		PA		1-1	78-34-21	D40694J	27			SM00015		9		ALL
6052	20		PA		1-1	78-34-21	D40694J	30			SM00015		9		ALL
6053	20		PA		1-11	78-34-21	D40696J	21			D40694J	29			YC051-YD158
6053	20		PA		1-10	78-34-21	D40696J	21			D40694J	29			YL951-YR328
6087	20		PA		2-1	47-30-11	D40700J	31			D10916	D1			YL951-YR328
6088	20		PA		1-8	47-30-11	D10916	D2			GD00524	DC..	1A		YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0080

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0080	286A0080			J24 BOX (continued)											
6103	18		PA		2-2	78-32-61	TB0024Y	B007	1D		GD00534	DC..	1D		YL951-YN235, YN237-YN260
6103	18		PA		2-1	78-32-61	TB0024Y	B007	1D		GD00534	DC..	1D		YN236, YN501-YR314
6103	18		PA		2-0	78-32-61	TB0024Y	B007	1D		GD00534	DC..	1D		YR315-YR328
6104	20		CQ		1-8	47-30-11	D40702J		31		D14156	A3			YL951-YR328
6105	20		CQ		2-0	47-30-11	D40692J		4		D14156	A2			YL951-YR328
6106	20		PA		1-7	47-30-11	D14156		A1		SM00009		9		YL951-YR328
6107	20		PA		1-7	47-30-11	D14156		X1		SM00009		9		YL951-YR328
6108	20		PA		1-5	47-30-11	D14156		X2		GD00524	DC..	1A		YL951-YR328
6109	20		PA		0-9	47-30-11	D40700J		30		SM00009		9		YL951-YR328
6113	20		PA		1-3	31-31-15	D10926		B3		GD00544	DC..	1		YL955-YL999, YN236-YR328
6114	22		PA		1-0	44-21-22	D13132		B2		D40702J		18		YN501-YR328
6115	22		PA		1-6	44-21-22	D13132		B3		D40698J		36		YN501-YR328
6501	24		PK		1-7	31-31-15	D40694J		1		D10926		B2		ALL
6502	24		PK		1-8	31-31-15	D10926		B1		TB0024Z	A013	1A		YC051-YD158
6502	24		PK		1-5	31-31-15	D10926		B1		TB0024Z	A013	1A		YL951-YR328
6503	24		PK		1-11	31-31-15	D40700J		2		TB0024Z	A013	1A		YC051-YD158
6503	24		PK		1-10	31-31-15	D40700J		2		TB0024Z	A013	1A		YL951-YR328
6504	22		PA		1-11	31-31-11	D01805		A3		GD00524	DC..	1A		YC051-YD158
6504	22		PA		1-6	31-31-11	D01805		A3		GD00524	DC..	1A		YL951-YR328
6505	22		PA		2-4	31-31-11	D40700J		8		D01805		A2		YC051-YD158
6505	22		PA		1-3	31-31-11	D40700J		8		D01805		A2		YL951-YR328
6506	22		PA		2-1	31-31-11	D01805		X1		TB0024Z	A013	1A		ALL
6507	22		PA		2-4	31-31-11	D40700J		20		D01805		X2		YC051-YD158
6507	22		PA		1-3	31-31-11	D40700J		20		D01805		X2		YL951-YR328
6508	22		PA		2-3	31-31-11	D40698J		4		TB0024Z	B013	1A		YC051-YN236, YN501-YR314
6508	22		PA		2-2	31-31-11	D40698J		4		TB0024Z	B013	1A		YR315-YR328
6509	22		PA		1-9	31-31-11	D10916		C1		TB0024Z	B013	1A		YC051-YD158
6509	22		PA		1-6	31-31-11	D10916		C1		TB0024Z	B013	1A		YL951-YR328
6510	22		PA		1-8	31-31-11	D10916		C2		GD00524	DC..	1A		ALL
6511	22		PA		1-11	31-31-11	D40700J		1		TB0024Z	B013	1A		YC051-YD158
6511	22		PA		1-10	31-31-11	D40700J		1		TB0024Z	B013	1A		YL951-YR328
6512	22		PA		2-3	31-31-11	D40698J		3		TB0024Z	A013	1A		YC051-YN236, YN501-YR314
6512	22		PA		2-2	31-31-11	D40698J		3		TB0024Z	A013	1A		YR315-YR328
6513	24		G6		1-8	34-41-11	D40694J		13		D10916		D2		YC051-YC052
6514	20		G5		1-8	34-41-11	D10916		D1		GD00524	DC..	1A		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W0080

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0080	286A0080			J24 BOX (continued)											
6515	22		PA		2-1	23-34-01	D40702J		14		D10525		X1		YC051-YD158
6515	22		PA		1-5	23-34-01	D40702J		14		D10525		X1		YL951-YN260
6515	22		PA		1-5	44-21-26	D40702J		30		D10525		X1		YN501-YR328
6516	22		PA		2-1	23-34-01	D40702J		15		D10525		X2		YC051-YD158
6516	22		PA		1-5	23-34-01	D40702J		15		D10525		X2		YL951-YN260
6516	22		PA		1-5	44-21-26	D40702J		15		D10525		X2		YN501-YR328
6517	20		PA		2-1	23-34-01	D40702J		23		D10525		A1		YC051-YD153
6517	20		G5		2-1	23-34-01	D40702J		23		D10525		A1		YD154-YD157
6518	20		PA		2-1	23-34-01	D40702J		21		D10525		A2		YC051-YC053
6518	20		PA		1-11	23-34-01	D40694J		4		D10525		A2		YC054-YD153
6518	20		G5		1-11	23-34-01	D40694J		4		D10525		A2		YD154-YD157
6525	20		PA		2-1	23-34-01	D40702J		22		D10525		B1		YC051-YD153
6525	20		G5		2-1	23-34-01	D40702J		22		D10525		B1		YD154-YD158
6525	20		G5		1-5	23-34-01	D40702J		22		D10525		B1		YL951-YN260
6525	20		G5		1-5	44-21-26	D40702J		22		D10525		B1		YN501-YR328
6526	20		PA		2-1	23-34-01	D40702J		13		D10525		B2		YC051-YC053
6526	20		PA		1-11	23-34-01	D40694J		3		D10525		B2		YC054-YD153
6526	20		G5		1-11	23-34-01	D40694J		3		D10525		B2		YD154-YD158
6526	20		G5		1-5	23-34-01	D40702J		13		D10525		B2		YL951-YN260
6526	20		G5		1-5	44-21-26	D40702J		13		D10525		B2		YN501-YR328
6530	22		PA		1-11	31-31-11	D40700J		21		TB0024Z	A013	1A		YC051-YD158
6530	22		PA		1-10	31-31-11	D40700J		21		TB0024Z	A013	1A		YL951-YR328
6542	24		PK		2-9	34-49-11	D40698J		25		D10847		7		YC053-YD158
6542	24		PK		2-10	34-49-11	D40698J		25		D10847		7		YL951-YR328
6543	24		PK		2-9	34-49-11	D40698J		26		D10847		12		YC053-YD158
6543	24		PK		2-10	34-49-11	D40698J		26		D10847		12		YL951-YR328
6544	24		PK		2-9	34-49-11	D40698J		30		D10847		8		YC053-YD158
6544	24		PK		2-10	34-49-11	D40698J		30		D10847		8		YL951-YR328
6545	24		PK		2-9	34-49-11	D40698J		31		D10847		6		YC053-YD158
6545	24		PK		2-10	34-49-11	D40698J		31		D10847		6		YL951-YR328
6550	22		PA		1-6	23-32-14	D12758		D2		D40702J		18		YD158
6550	22		PA		1-2	23-32-14	D12758		D2		D40702J		18		YL951-YN260
6551	22		PA		2-10	23-32-14	D12758		D1		GD00534	DC..	1A		YD158
6551	22		PA		2-9	23-32-14	D12758		D1		GD00534	DC..	1A		YL951-YN260
6552	20		PA		1-5	23-32-14	D40700J		15		D40694J		10		YD158
6552	20		PA		1-4	23-32-14	D40700J		15		D40694J		10		YL951-YN260
6552	20		PA		1-4	44-21-22	D40700J		15		D40694J		10		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0080

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0082	286A0082			J39 JUNCTION BOX-PLATE A											
0001	22		PA		2-1	27-62-11	D43900J		1		TB3901Y	A001	1A		YL953-YL999, YR301-YR328
0002	20		PA		1-10	27-62-11	D43906J		1		TB3901Z	A005	1A		YL953-YL999, YR301-YR328
0003	22		PA		2-1	27-62-11	D43900J		7		TB3901Z	A005	1A		YL953-YL999, YR301-YR328
0004	22		PA		1-4	27-62-11	TB3901Y	A001	1A		D13944		D2		YL953-YL999, YR301-YR328
0005	22		PA		1-4	27-62-11	TB3901Z	A005	1A		D13944		A2		YL953-YL999, YR301-YR328
0006	20		PA		1-8	27-62-11	GD08200	DC..	1A		D13944		C2		YL953-YL999, YR301-YR328
0007	22		PA		1-4	27-62-11	TB3901Z	A005	1A		D13944		X1		YL953-YL999, YR301-YR328
0008	22		PA		1-0	27-62-11	D13946		B1		D13944		X2		YL953-YL999, YR301-YR328
0009	22		PA		1-5	27-62-11	TB3901Z	B005	1A		D13946		D2		YL953-YL999, YR301-YR328
0010	20		PA		1-8	27-62-11	D13946		B2		GD08200	DC..	1A		YL953-YL999, YR301-YR328
0011	20		PA		1-8	27-62-11	D13946		C2		GD08200	DC..	1A		YL953-YL999, YR301-YR328
0012	22		PA		1-5	27-62-11	SM00024		W		D43900J		4		YL953-YL999, YR301-YR328
0013	22		PA		1-6	27-62-11	D13946		X1		TB3901Y	B011	1A		YL953-YL999, YR301-YR328
0014	22		PA		2-2	27-62-11	D43900J		6		TB3901Y	B011	1A		YL953-YL999, YR301-YR328
0015	22		PA		1-0	27-62-11	D13952		X2		SM00024		W		YL953-YL999, YR301-YR328
0016	22		PA		1-3	27-62-11	D13952		X1		TB3901Y	B011	1A		YL953-YL999, YR301-YR328
0017	20		PA		1-9	27-62-11	D13948		X2		D43906J		2		YL953-YL999, YR301-YR328
0018	22		PA		1-3	27-62-11	D13948		X1		TB3901Z	A005	1A		YL953-YL999, YR301-YR328
0019	20		PA		1-9	27-62-11	D13948		D2		GD08200	DC..	1A		YL953-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W0080

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0082	286A0082			J39 JUNCTION BOX-PLATE A (continued)											
0020	22		PA		1-9	27-62-11	D13948		C2		D43906J		5		YL953-YL999, YR301-YR328
0021	22		PA		1-3	27-62-11	D13948		B2		D13946		C1		YL953-YL999, YR301-YR328
0022	22		PA		1-3	27-62-11	D13948		A2		TB3901Z	B005	1A		YL953-YL999, YR301-YR328
0023	22		PA		1-9	27-62-11	D13948		A3		TB3901Z	A013	1A		YL953-YL999, YR301-YR328
0024	22		PA		1-9	27-62-11	D13948		B3		TB3901Z	A013	1A		YL953-YL999, YR301-YR328
0025	22		PA		1-9	27-62-11	D13948		C1		TB3901Z	A013	1A		YL953-YL999, YR301-YR328
0026	22		PA		1-4	27-62-11	D13948		D1		TB3901Y	B009	1A		YL953-YL999, YR301-YR328
0027	22		PA		1-8	27-62-11	D13952		A1		TB3901Z	A013	1A		YL953-YL999, YR301-YR328
0028	22		PA		1-9	27-62-11	TB3901Y	A001	1A		D13950		X1		YL953-YL999, YR301-YR328
0029	22		PA		1-10	27-62-11	TB3901Y	A011	1A		D13950		X2		YL953-YL999, YR301-YR328
0030	22		PA		1-10	27-62-11	TB3901Y	A011	1A		D13950		A2		YL953-YL999, YR301-YR328
0031	22		PA		1-11	27-62-11	TB3901Y	A011	1A		TB3901Z	A013	1A		YL953-YL999, YR301-YR328
0032	22		PA		1-6	27-62-11	D13950		B2		D43906J		3		YL953-YL999, YR301-YR328
0033	20		PA		1-4	27-62-11	D13950		B1		GD08200	DC..	1A		YL953-YL999, YR301-YR328
0034	20		PA		1-4	27-62-11	D13950		A1		GD08200	DC..	1A		YL953-YL999, YR301-YR328
0035	22		PA		1-5	27-62-11	TB3901Y	B009	1A		D13940		X2		YL953-YL999, YR301-YR328
0036	20		PA		1-8	27-62-11	D13940		D1		GD08200	DC..	1A		YL953-YL999, YR301-YR328
0037	20		PA		1-8	27-62-11	D13940		C3		GD08200	DC..	1A		YL953-YL999, YR301-YR328
0038	22		PA		1-5	27-62-11	D13940		A2		TB3901Y	B001	1A		YL953-YL999, YR301-YR328

WIRE LIST
D280A108

91-21-11
Section W0080
Page 16
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0082	286A0082			J39 JUNCTION BOX-PLATE A (continued)											
0039	22		PA		1-5	27-62-11	D13940		B2		TB3901Y	B001	1A		YL953-YL999, YR301-YR328
0040	22		PA		1-5	27-62-11	D13940		D2		TB3901Z	B005	1A		YL953-YL999, YR301-YR328
0041	22		PA		1-5	27-62-11	D13940		C2		TB3901Y	A003	1A		YL953-YL999, YR301-YR328
0042	22		PA		1-5	27-62-11	D13940		X1		TB3901Y	A009	1A		YL953-YL999, YR301-YR328
0043	22		PA		1-4	27-62-11	D13944		D1		TB3901Y	B003	1A		YL953-YL999, YR301-YR328
0044	22		PA		1-4	27-62-11	D13944		A1		TB3901Y	B001	1A		YL953-YL999, YR301-YR328
0045	22		PA		1-0	27-62-11	D13944		C3		D13946	A2			YL953-YL999, YR301-YR328
0046	22		PA		1-4	27-62-11	D13944		C1		TB3901Z	B005	1A		YL953-YL999, YR301-YR328
0047	22		PA		1-4	27-62-11	TB3901Z	B005	1A		D13942	D2			YL953-YL999, YR301-YR328
0048	22		PA		1-4	27-62-11	TB3901Y	A003	1A		D13942	C2			YL953-YL999, YR301-YR328
0049	22		PA		1-4	27-62-11	TB3901Y	B003	1A		D13942	A2			YL953-YL999, YR301-YR328
0050	22		PA		1-4	27-62-11	TB3901Y	B003	1A		D13942	B2			YL953-YL999, YR301-YR328
0051	22		PA		1-5	27-62-11	TB3901Y	A009	1A		D13942	X1			YL953-YL999, YR301-YR328
0052	22		PA		1-5	27-62-11	TB3901Y	B009	1A		D13942	X2			YL953-YL999, YR301-YR328
0053	20		PA		1-8	27-62-11	D13942		D1		GD08200	DC..	1A		YL953-YL999, YR301-YR328
0054	20		PA		1-8	27-62-11	D13942		C3		GD08200	DC..	1A		YL953-YL999, YR301-YR328
0055	22		PA		2-2	27-62-11	D43900J		3		TB3901Y	A009	1A		YL953-YL999, YR301-YR328
0056	22		PA		1-10	27-62-11	D43906J		4		TB3901Y	A003	1A		YL953-YL999, YR301-YR328
0057	22		PA		1-8	27-62-11	D13946		A1		TB3901Z	A013	1A		YL953-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W0080

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0082	286A0082			J39 JUNCTION BOX-PLATE A (continued)											
0067	22		PA		1-2	27-62-11	D13946		D3		D13952		A2		YL953-YL999, YR301-YR328
0116	22		PA		1-0	27-62-11	D13946		X2		SM00024		W		YL953-YL999, YR301-YR328
0117	22		PA		1-5	23-27-31	D12669		6		D43906J		21		YL951-YL954, YN231-YN235
0118	22		PA		1-5	23-27-31	D12669		12		D43906J		20		YL951-YL954, YN231-YN235
1001	20		X1	AA	1-8	27-62-11	D13940		A1		TB3901Y	A017	1A		YL953-YL999, YR301-YR328
1001Z				AA	0-0	27-62-11	D13940		DED		GB03901	ST..	1A		YL953-YL999, YR301-YR328
1002	20		X1	AB	1-8	27-62-11	D13940		B1		TB3901Y	B017	1A		YL953-YL999, YR301-YR328
1002Z				AB	0-0	27-62-11	D13940		DED		GB03901	ST..	1A		YL953-YL999, YR301-YR328
1005	20		X1	AC	1-7	27-62-11	D13942		A1		TB3901Y	A019	1A		YL953-YL999, YR301-YR328
1005Z				AC	0-0	27-62-11	D13942		DED		GB03901	ST..	1A		YL953-YL999, YR301-YR328
1006	20		X1	AD	1-7	27-62-11	D13942		B1		TB3901Y	B019	1A		YL953-YL999, YR301-YR328
1006Z				AD	0-0	27-62-11	D13942		DED		GB03901	ST..	1A		YL953-YL999, YR301-YR328
1009	20		X1	AE	1-3	27-62-11	D43908J		1		TB3901Y	A017	1A		YL953-YL999, YR301-YR328
1009Z				AE	0-0	27-62-11	D43908J		PERS	1A	GB03901	ST..	1A		YL953-YL999, YR301-YR328
1010	20		X1	AF	1-3	27-62-11	D43908J		2		TB3901Z	A021	1A		YL953-YL999, YR301-YR328
1010Z				AF	0-0	27-62-11	D43908J		PERS	1A	GB03901	ST..	1A		YL953-YL999, YR301-YR328
1011	20		X1	AG	1-3	27-62-11	D43908J		3		TB3901Y	A019	1A		YL953-YL999, YR301-YR328
1011Z				AG	0-0	27-62-11	D43908J		PERS	1A	GB03901	ST..	1A		YL953-YL999, YR301-YR328
1012	20		X1	AH	1-3	27-62-11	D43908J		4		TB3901Z	B013	1A		YL953-YL999, YR301-YR328

WIRE LIST
D280A108

91-21-11
Section W0080
Page 18
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W0082	286A0082	J39 JUNCTION BOX-PLATE A (continued)			
1012Z		AH	0-0 27-62-11 D43908J	PERS 1A	GB03901 ST.. 1A YL953-YL999, YR301-YR328
1013	20 X1	AK	1-3 27-62-11 D43908J	5	TB3901Y B017 1A YL953-YL999, YR301-YR328
1013Z		AK	0-0 27-62-11 D43908J	PERS 1A	GB03901 ST.. 1A YL953-YL999, YR301-YR328
1014	20 X1	AL	1-3 27-62-11 D43908J	6	TB3901Z A021 1A YL953-YL999, YR301-YR328
1014Z		AL	0-0 27-62-11 D43908J	PERS 1A	GB03901 ST.. 1A YL953-YL999, YR301-YR328
1015	20 X1	AM	1-3 27-62-11 D43908J	7	TB3901Y B019 1A YL953-YL999, YR301-YR328
1015Z		AM	0-0 27-62-11 D43908J	PERS 1A	GB03901 ST.. 1A YL953-YL999, YR301-YR328
1016	20 X1	AN	1-3 27-62-11 D43908J	8	TB3901Z B013 1A YL953-YL999, YR301-YR328
1016Z		AN	0-0 27-62-11 D43908J	PERS 1A	GB03901 ST.. 1A YL953-YL999, YR301-YR328
1017	20 PA		1-8 27-62-11 TB3901Z	B013 1A	GD08202 DC.. 1A YL953-YL999, YR301-YR328
1018	20 X1	AP	1-4 27-62-11 D43910J	1	TB3901Y A019 1A YL953-YL999, YR301-YR328
1018Z		AP	0-0 27-62-11 D43910J	PERS 1A	GB03901 ST.. 1A YL953-YL999, YR301-YR328
1019	20 X1	AQ	1-4 27-62-11 D43910J	2	TB3901Z B013 1A YL953-YL999, YR301-YR328
1019Z		AQ	0-0 27-62-11 D43910J	PERS 1A	GB03901 ST.. 1A YL953-YL999, YR301-YR328
1020	20 X1	AR	1-4 27-62-11 D43910J	3	TB3901Y A017 1A YL953-YL999, YR301-YR328
1020Z		AR	0-0 27-62-11 D43910J	PERS 1A	GB03901 ST.. 1A YL953-YL999, YR301-YR328
1021	20 X1	AS	1-4 27-62-11 D43910J	4	TB3901Z A021 1A YL953-YL999, YR301-YR328
1021Z		AS	0-0 27-62-11 D43910J	PERS 1A	GB03901 ST.. 1A YL953-YL999, YR301-YR328
1022	20 X1	AT	1-4 27-62-11 D43910J	5	TB3901Y B019 1A YL953-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W0080

Page 19

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0082	286A0082			J39 JUNCTION BOX-PLATE A (continued)											
1022Z				AT	0-0	27-62-11	D43910J	PERS	1A		GB03901	ST..	1A		YL953-YL999, YR301-YR328
1023	20	X1		AU	1-4	27-62-11	D43910J		6		TB3901Z	B013	1A		YL953-YL999, YR301-YR328
1023Z				AU	0-0	27-62-11	D43910J	PERS	1A		GB03901	ST..	1A		YL953-YL999, YR301-YR328
1024	20	X1		AV	1-4	27-62-11	D43910J		7		TB3901Y	B017	1A		YL953-YL999, YR301-YR328
1024Z				AV	0-0	27-62-11	D43910J	PERS	1A		GB03901	ST..	1A		YL953-YL999, YR301-YR328
1025	20	X1		AY	1-4	27-62-11	D43910J		8		TB3901Z	A021	1A		YL953-YL999, YR301-YR328
1025Z				AY	0-0	27-62-11	D43910J	PERS	1A		GB03901	ST..	1A		YL953-YL999, YR301-YR328
1026	20	PA			1-8	27-62-11	TB3901Z	A021	1A		GD08202	DC..	1A		YL953-YL999, YR301-YR328
2201B	24	Y2		KA	1-5	23-27-39	D12669		9		D43906J		30		YL951-YL954, YN231-YN235
2201R	24	Y2		KA	0-0	23-27-39	D12669		14		D43906J		29		YL951-YL954, YN231-YN235
2201Z				KA	0-0	23-27-39	GB03901	ST..	1A		D43906J		28		YL951-YL954, YN231-YN235
2202B	24	Y2		KB	1-5	23-27-39	D12669		11		D43906J		27		YL951-YL954, YN231-YN235
2202R	24	Y2		KB	0-0	23-27-39	D12669		7		D43906J		26		YL951-YL954, YN231-YN235
2202Z				KB	0-0	23-27-39	GB03901	ST..	1A		D43906J		25		YL951-YL954, YN231-YN235
2203B	24	Y2		KC	1-5	23-27-39	D12669		10		D43906J		23		YL951-YL954, YN231-YN235
2203R	24	Y2		KC	0-0	23-27-39	D12669		8		D43906J		24		YL951-YL954, YN231-YN235
2203Z				KC	0-0	23-27-39	GB03901	ST..	1A		D43906J		22		YL951-YL954, YN231-YN235
W0084	286A0084			J39 JUNCTION BOX-PLATE B											
0058	24	PK			1-6	23-42-14	D43924J	B03			D43922J	B04			YN501-YR328
0059	24	PK			1-7	23-42-14	D43922J	A03			D12945	X2			YN501-YR328
0060	24	PK			1-7	23-42-14	D43922J	A04			D12945	X1			YN501-YR328

WIRE LIST
D280A108

91-21-11
Section W0080
Page 20
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0084		286A0084				J39 JUNCTION BOX-PLATE B (continued)									
	2001B	24	Y2	GA	1-8	23-42-14	D43924J	B01			D12945	D2			YN501-YR328
	2001R	24	Y2	GA	0-0	23-42-14	D43924J	A01			D12945	C2			YN501-YR328
	2001Z			GA	0-0	23-42-14	D43924J			AA	D12945			AB	YN501-YR328
	2002B	24	Y2	GB	1-8	23-42-14	D43924J	B02			D12945	B2			YN501-YR328
	2002R	24	Y2	GB	0-0	23-42-14	D43924J	A02			D12945	A2			YN501-YR328
	2002Z			GB	0-0	23-42-14	D43924J			AA	D12945			AB	YN501-YR328
	2003B	24	Y2	GC	1-7	23-42-14	D12945	D1			D43922J	B01			YN501-YR328
	2003R	24	Y2	GC	0-0	23-42-14	D12945	C1			D43922J	A01			YN501-YR328
	2003Z			GC	0-0	23-42-14	D12945			AD	D43922J			AC	YN501-YR328
	2004B	24	Y2	GD	1-7	23-42-14	D12945	B1			D43922J	B02			YN501-YR328
	2004R	24	Y2	GD	0-0	23-42-14	D12945	A1			D43922J	A02			YN501-YR328
	2004Z			GD	0-0	23-42-14	D12945			AD	D43922J			AC	YN501-YR328
	FRAA				0-0	23-42-14	D43924J			AA	D43924J	PERG	1F		YN501-YR328
	FRAB				0-0	23-42-14	D12945			AB	GB03902	ST..	1A		YN501-YR328
	FRAC				0-0	23-42-14	D43922J			AC	D43922J	PERG	1F		YN501-YR328
	FRAD				0-0	23-42-14	D12945			AD	GB03902	ST..	1A		YN501-YR328
W0088		286A0088				J48 INTEGRATION PANEL WIRING									
	0001	22	PA		1-8	21-27-21	D48102J	A01			D48130J	A02			ALL
	0003	22	PA		1-7	21-27-21	D48130J	A03			D48124J	A02			ALL
	0004	24	PK		1-11	21-27-21	D48138J	A01			TB1882Y	A001	1A		ALL
	0005	24	PK		1-10	21-27-21	D48130J	A01			TB1882Y	A001	1A		ALL
	0006	24	PK		1-8	21-27-21	D48124J	A01			TB1882Y	A001	1A		ALL
	0007	22	G5		1-8	21-27-21	D48102J	A02			TB1882Y	A005	1A		ALL
	0008	22	G5		1-6	21-27-21	D48112J	A01			TB1882Y	A005	1A		ALL
	0009	22	G5		1-6	21-27-21	D48124J	A03			TB1882Y	A005	1A		ALL
	0010	24	G6		1-11	21-27-31	D48120J	A01			D48126J	A02			ALL
	0011	22	G5		1-11	21-27-31	D48104J	A01			D48116J	A01			ALL
	0012	22	G5		2-2	21-27-31	D48116J	B01			D48126J	A01			ALL
	0013	22	G5		1-11	21-27-31	D48120J	A02			TB1884Y	A001	1A		ALL
	0014	22	G5		2-2	21-27-31	D48116J	B10			TB1884Y	A001	1A		ALL
	0015	22	G5		2-2	21-27-31	D48116J	A10			TB1884Y	A001	1A		ALL
	0016	24	PK		1-11	21-42-11	D48120J	A03			D48126J	A04			ALL
	0017	24	PK		1-5	21-42-11	D48124J	A04			D48112J	B01			ALL
	0018	20	PA		1-4	21-42-11	D48124J	B02			D48104J	A08			ALL
	0019	20	PA		1-4	21-42-11	D48124J	B03			D48104J	A09			ALL
	0020	24	B6		1-7	21-43-21	D48106J	A01			D48122J	A02			ALL
	0021	24	B6		1-7	21-43-21	D48106J	A02			D48122J	A03			YC051-YD158
	0022	20	G5		1-8	27-53-11	D48100J	A06			D48124J	B08			ALL

WIRE LIST

D280A108

91-21-11

Section W0080

Page 21

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0088	286A0088				J48 INTEGRATION PANEL WIRING (continued)											
0023	24		PK		1-7	24-33-11		D48102J	A04			D48112J	A02			ALL
0024	24		B6		1-6	24-33-11		D48106J	A09			D48108J	A05			ALL
0026	20		G5		1-8	27-53-11		D48100J	A01			D48124J	A08			ALL
0027	20		G5		1-8	27-53-11		D48100J	A02			D48124J	A09			ALL
0028	20		CQ		1-10	28-21-11		D48106J	A10			D48120J	A04			ALL
0029	20		CQ		1-11	28-21-11		D48120J	A05			D48122J	A06			ALL
0030	22		CQ		1-6	28-41-11		D48132J	A04			D48128J	A01			ALL
0031	22		G5		1-8	29-11-12		D48124J	A10			D48100J	A03			ALL
0032	22		G5		1-8	29-11-12		D48124J	B01			D48100J	A04			ALL
0033	20		G5		2-0	29-33-11		D48100J	A05			D48120J	A06			ALL
0034	22		PA		1-7	30-11-11		D48102J	A07			D48112J	A03			ALL
0035	22		PA		1-7	30-11-11		D48102J	A08			D48112J	B03			ALL
0036	22		CQ		1-9	30-11-11		D48106J	B01			D48134J	A01			ALL
0037	22		PA		1-9	30-11-11		D48102J	A09			TB1882Y	B001	1A		ALL
0038	22		PA		1-8	30-11-11		D48122J	A07			TB1882Y	B001	1A		ALL
0039	22		PA		1-8	30-11-11		D48122J	A08			TB1882Y	B001	1A		ALL
0040	22		PA		2-1	30-11-11		D48132J	A05			TB1882Y	B001	1A		ALL
0041	20		PA		1-11	30-21-11		D48106J	B02			D48110J	A01			ALL
0042	20		PA		1-11	30-21-11		D48106J	B05			D48110J	A04			ALL
0043	22		CQ		1-8	30-31-11		D48104J	A02			D40087J	A03			ALL
0044	22		PA		1-8	30-31-11		D48104J	A03			D40087J	A04			ALL
0045	22		PA		1-8	30-31-11		D48104J	A04			D40087J	A05			ALL
0046	22		PA		1-8	30-31-11		D48104J	A05			D40087J	A06			ALL
0047	22		PA		1-11	SPARE		D48104J	A07			D48116J	A03			ALL
0048	22		PA		1-6	32-64-21		D48122J	A09			D48114J	A04			ALL
0049	22		PA		1-6	32-64-21		D48122J	A10			D48114J	B04			ALL
0050	22		PA		1-7	34-21-16		D48114J	A07			TB1882Y	A003	1A		ALL
0051	22		PA		2-2	34-21-16		D48116J	A04			TB1882Y	A003	1A		ALL
0052	22		PA		1-7	34-21-16		D48112J	B04			TB1882Y	A003	1A		ALL
0053	22		PA		1-10	34-41-11		D40081J	A03			D40089J	A07			YC051-YC052
0054	22		PA		1-9	34-41-11		D48104J	A06			D40089J	A08			YC051-YC052
0055	22		PA		1-9	SPARE		D40089J	B01			D48116J	B04			YC051-YC052
0057	22		PA		1-10	34-41-11		D40081J	A08			D40091J	A03			YC051-YC052
0058	22		PA		1-10	34-41-11		D40081J	A09			D40091J	A04			YC051-YC052
0059	22		PA		1-10	34-41-11		D48114J	A03			D40091J	A05			YC051-YC052
0060	22		PA		1-10	34-41-11		D40081J	A10			D40091J	A06			YC051-YC052
0061	24		PK		1-10	34-41-11		D48112J	A04			D40091J	A07			YC051-YC052
0062	22		CQ		1-7	34-51-41		D40095J	A01			D48106J	B06			ALL
0063	22		PA		1-6	34-53-11		D48114J	A05			D40095J	A02			ALL

WIRE LIST

D280A108

91-21-11

Section W0080

Page 22

Nov 12/2012



WIRE LIST

91-21-11

Section W0080

Page 23

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0088	286A0088				J48 INTEGRATION PANEL WIRING (continued)											
0109R	22		PH		1-10	26-21-11		D48138J		B04		TB1882Y	B009	1A		ALL
0110R	22		PH		1-11	26-21-11		D48138J		B05		TB1884Y	B003	1A		ALL
0111R	22		PH		1-11	26-21-11		D48138J		B06		TB1884Y	A003	1A		ALL
0112R	22		PH		1-9	26-21-11		D48138J		B07		TB1884Y	B005	1A		ALL
0113R	22		PH		1-9	26-21-11		D48118J		A01		TB1884Y	B003	1A		ALL
0114R	22		PH		1-9	26-21-11		D48118J		A02		TB1884Y	A003	1A		ALL
0115R	22		PH		1-8	26-21-11		D48118J		A03		TB1884Y	B005	1A		ALL
0116R	22		PH		1-9	26-21-11		D48118J		A04		TB1884Y	B003	1A		ALL
0117R	22		PH		1-9	26-21-11		D48118J		A05		TB1884Y	A003	1A		ALL
0118R	22		PH		1-8	26-21-11		D48118J		A06		TB1884Y	B005	1A		ALL
0120	22		PA		1-6	24-22-11		D48102J		A03		D48124J	A05			ALL
0121	22		PA		1-6	24-28-11		D48124J		A06		D48106J	A03			ALL
0122	22		PA		1-6	24-28-11		D48124J		A07		D48106J	A04			ALL
0123	22		G5		1-8	SPARE		D48130J		A05		D48114J	B07			ALL
0124	22		G5		1-8	SPARE		D48130J		A06		D48114J	B08			ALL
0125	22		G5		1-8	SPARE		D48130J		A07		D48114J	B09			ALL
0126	22		G5		1-8	SPARE		D48130J		A08		D48114J	B10			ALL
0161	22		G5		1-8	21-27-21		D48130J		A09		D48112J	A10			YD160-YR328
0162	22		G5		1-9	21-27-21		D48130J		A10		TB1882Y	B007	1A		YD160-YR328
0163	22		G5		1-6	21-27-21		TB1882Y		B007	1A	D48112J	B10			YD160-YR328
0164	22		G5		1-5	21-27-21		D48114J		A08		TB1882Y	B007	1A		YD160-YR328
0165	24		G6		1-11	21-43-21		D48122J		B08		D48120J	B03			YD160-YR328
0201	20		PA		1-6	52-71-13		D48112J		A08		D48104J	B03			YC051-YD158, YL951-YL999, YR301-YR328 YN231-YN501
0201	20		PA		1-6	SPARE		D48112J		A08		D48104J	B03			YN231-YN501
0202	20		PA		1-6	52-71-13		D48112J		A06		D48104J	B02			ALL
0203	20		PA		1-6	52-71-13		D48112J		A05		TB1882Y	B019	1A		ALL
0204	20		PA		1-6	52-71-13		D48112J		A07		TB1882Y	A019	1A		ALL
0205	20		PA		1-5	52-71-13		TB1882Y		A019	1A	D48104J	B01			ALL
0206	20		PA		1-11	52-71-14		D48116J		B05		D48104J	B06			YC051-YD158, YL951-YL999, YR301-YR328 YN231-YN501
0206	20		PA		1-11	SPARE		D48116J		B05		D48104J	B06			YN231-YN501
0207	20		PA		1-11	52-71-14		D48116J		B09		D48104J	B05			ALL
0208	20		PA		2-0	52-71-14		D48116J		B08		TB1882Y	A019	1A		ALL
0209	20		PA		2-0	52-71-14		D48116J		B07		TB1882Y	B019	1A		ALL
0210	20		PA		1-5	52-71-14		D48104J		B04		TB1882Y	B019	1A		ALL
1001	24		Y1	AA	1-6	73-21-12		D48136J		A03		TB1882Y	B005	1A		ALL

WIRE LIST

D280A108

91-21-11
Section W0080
Page 24
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	FT-IN	Diagram	From				To				Effectivity
	GA	CO	TY				Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W0088	286A0088			J48 INTEGRATION PANEL WIRING (continued)											
1001Z				AA	0-0	73-21-12	D48136J	PERG	1F		GB01882	ST..	1A		ALL
1002	24	Y1		AB	1-9	73-21-12	D48134J	A02			TB1882Y	B005	1A		ALL
1002Z				AB	0-0	73-21-12	D48134J	PERG	1F		GB01882	ST..	1A		ALL
1003	24	Y1		AC	1-8	73-21-12	D48102J	A10			TB1882Y	B005	1A		ALL
1003Z				AC	0-0	73-21-12	D48102J	PERG	1F		GB01882	ST..	1A		ALL
1005	20	X1		AE	1-9	73-22-11	D48114J	A06			D48110J	A05			ALL
1005Z				AE	0-0	73-22-11	D48114J	PERG	1F		D48110J	PERG	1F		ALL
1006	20	X1		AF	1-11	74-11-11	D48122J	B01			D48110J	A06			ALL
1006Z				AF	0-0	74-11-11	D48122J	PERG	1F		D48110J	PERG	1F		ALL
2001B	24	Y2		GA	1-10	SPARE	D40081J	A02			D40089J	A02			YC051-YC052
2001R	24	Y2		GA	0-0	SPARE	D40081J	A01			D40089J	A01			YC051-YC052
2001Z				GA	0-0	SPARE	D40081J	PERG	1F		D40089J	PERG	1F		YC051-YC052
2002B	22	X2		GB	2-0	24-22-31	D48132J	A03			D48122J	A05			ALL
2002R	22	X2		GB	0-0	24-22-31	D48132J	A02			D48122J	A04			ALL
2002Z				GB	0-0	24-22-31	D48132J	DED			D48122J	DED			ALL
2003B	24	Y2		GC	1-6	24-31-11	D48106J	A06			D48108J	A02			YC051-YD170, YN231
2003B	20	X2		GC	1-6	24-31-11	D48106J	A06			D48108J	A02			YL951-YL999, YN232-YR328
2003R	24	Y2		GC	0-0	24-31-11	D48106J	A05			D48108J	A01			YC051-YD170, YN231
2003R	20	X2		GC	0-0	24-31-11	D48106J	A05			D48108J	A01			YL951-YL999, YN232-YR328
2003Z				GC	0-0	24-31-11	D48106J	DED			D48108J	DED			ALL
2004B	24	Y2		GD	1-6	24-31-12	D48106J	A08			D48108J	A04			YC051-YD170, YN231
2004B	20	X2		GD	1-6	24-31-12	D48106J	A08			D48108J	A04			YL951-YL999, YN232-YR328
2004R	24	Y2		GD	0-0	24-31-12	D48106J	A07			D48108J	A03			YC051-YD170, YN231
2004R	20	X2		GD	0-0	24-31-12	D48106J	A07			D48108J	A03			YL951-YL999, YN232-YR328
2004Z				GD	0-0	24-31-12	D48106J	DED			D48108J	DED			ALL
2005B	22	X2		GE	1-7	28-41-11	D40087J	A02			D48128J	A03			ALL
2005R	22	X2		GE	0-0	28-41-11	D40087J	A01			D48128J	A02			ALL
2005Z				GE	0-0	28-41-11	D40087J	PERG	1F		D48128J	PERG	1F		ALL
2006B	22	X2		GF	1-7	28-41-11	D48116J	A02			D48128J	A04			ALL
2006R	22	X2		GF	0-0	28-41-11	D48116J	B02			D48128J	A05			ALL
2006Z				GF	0-0	28-41-11	D48116J	PERG	1F		D48128J	PERG	1F		ALL
2007B	22	X2		GG	1-11	30-21-11	D48106J	B04			D48110J	A03			ALL
2007R	22	X2		GG	0-0	30-21-11	D48106J	B03			D48110J	A02			ALL
2007Z				GG	0-0	30-21-11	D48106J	DED			D48110J	DED			ALL
2008B	24	Y2		GH	1-8	34-21-14	D40089J	A06			D40087J	A10			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W0080

Page 25

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0088	286A0088			J48 INTEGRATION PANEL WIRING (continued)											
2008R	24	Y2	GH		0-0	34-21-14	D40089J	A05			D40087J	A09			YC051-YC052
2008Z			GH		0-0	34-21-14	D40089J	PERG	1F		D40087J	PERG	1F		YC051-YC052
2010B	24	7K	GJ		1-10	34-41-11	D40081J	A05			D40089J	A10			YC051-YC052
2010W	24	7K	GJ		0-0	34-41-11	D40081J	A04			D40089J	A09			YC051-YC052
2010Z			GJ		0-0	34-41-11	D40081J	PERG	1F		D40089J	PERG	1F		YC051-YC052
2011B	24	Y2	GK		1-10	34-41-11	D40081J	A07			D40091J	A02			YC051-YC052
2011R	24	Y2	GK		0-0	34-41-11	D40081J	A06			D40091J	A01			YC051-YC052
2011Z			GK		0-0	34-41-11	D40081J	PERG	1F		D40091J	PERG	1F		YC051-YC052
2012B	22	X2	GL		1-7	34-61-14	D48128J	A07			D40087J	B02			ALL
2012R	22	X2	GL		0-0	34-61-14	D48128J	A06			D40087J	B01			ALL
2012Z			GL		0-0	34-61-14	D48128J	PERG	1F		D40087J	PERG	1F		ALL
2013B	24	Y2	GM		1-5	73-21-11	D48114J	B01			D48136J	A02			ALL
2013R	24	Y2	GM		0-0	73-21-11	D48114J	A01			D48136J	A01			ALL
2013Z			GM		0-0	73-21-11	D48114J	PERG	1F		D48136J	PERG	1F		ALL
2014B	24	Y2	GN		1-8	34-21-13	D40089J	A04			D40087J	A08			YC051-YC052
2014R	24	Y2	GN		0-0	34-21-13	D40089J	A03			D40087J	A07			YC051-YC052
2014Z			GN		0-0	34-21-13	D40089J	PERG	1F		D40087J	PERG	1F		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W0080

Page 26 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0094		286A0094				J4 JUNCTION BOX									
0001	22	PA			1-10	22-13-11	D40610J	13			R00064	13	C		YC051-YC057
0001	22	PA			2-3	22-13-11	D40610J	13			R00064	13	C		YC058-YC064
0001	22	PA			2-2	22-13-11	D40610J	13			R00064	13	C		YC065-YR328
0002	22	G5			2-7	22-13-11	D40610J	12			R00064	14	C		YC051-YC064
0002	22	G5			2-6	22-13-11	D40610J	12			R00064	14	C		YC065-YR328
0021	20	PA			1-2	27-53-12	R00058	X1	C		R00057	D2	C		YC051-YC057
0021	20	PA			1-4	27-53-12	R00058	X1	C		R00057	D2	C		YC058-YR328
0022	20	PA			2-0	27-53-12	R00058	X2	C		D40610J	5			YC051-YC057
0022	20	PA			2-2	27-53-12	R00058	X2	C		D40610J	5			YC058-YC064
0022	20	PA			2-1	27-53-12	R00058	X2	C		D40610J	5			YC065-YR328
0023	16	PA			1-2	27-53-12	D40614J	1			R00058	A1	C	*	YC051-YC064
0023	16	PA			1-3	27-53-12	D40614J	1			R00058	A1	C	*	YC065-YR328
0024	16	PA			1-10	27-53-12	R00058	A1	C	*	R00057	B1	C		YC051-YC064
0024	16	PA			1-3	27-53-12	R00058	A1	C	*	R00057	B1	C		YC065-YR328
0025	16	PA			3-6	27-53-12	R00058	A2	C	*	D40602J	1			YC051-YC064
0025	16	PA			3-5	27-53-12	R00058	A2	C	*	D40602J	1			YC065-YR328
0026	16	PA			2-0	27-53-12	R00058	A2	C	*	R00057	A2	C		ALL
0027	16	PA			2-6	27-53-12	R00058	B1	C	*	D40614J	2			ALL
0028	16	PA			1-2	27-53-12	R00058	B1	C	*	R00057	A1	C		YC051-YC064
0028	16	PA			1-4	27-53-12	R00058	B1	C	*	R00057	A1	C		YC065-YR328
0029	16	PA			1-11	27-53-12	R00058	B2	C	*	D40602J	2			YC051-YC064
0029	16	PA			2-6	27-53-12	R00058	B2	C	*	D40602J	2			YC065-YR328
0030	16	PA			2-4	27-53-12	R00058	B2	C	*	R00057	B2	C		YC051-YC064
0030	16	PA			1-11	27-53-12	R00058	B2	C	*	R00057	B2	C		YC065-YR328
0031	16	PA			1-3	27-53-12	R00058	C1	C	*	D40614J	3			YC051-YC064
0031	16	PA			1-2	27-53-12	R00058	C1	C	*	D40614J	3			YC065-YR328
0032	16	PA			2-9	27-53-12	R00058	C1	C	*	R00057	C1	C		YC051-YC064
0032	16	PA			1-11	27-53-12	R00058	C1	C	*	R00057	C1	C		YC065-YR328
0033	16	PA			3-5	27-53-12	R00058	C2	C	*	D40602J	3			YC051-YC064
0033	16	PA			3-4	27-53-12	R00058	C2	C	*	D40602J	3			YC065-YR328
0034	16	PA			2-1	27-53-12	R00058	C2	C	*	R00057	C2	C		YC051-YC064
0034	16	PA			2-0	27-53-12	R00058	C2	C	*	R00057	C2	C		YC065-YR328
0035	20	PA			1-2	27-53-12	R00058	D2	C		R00057	X1	C		YC051-YC057
0035	20	PA			1-4	27-53-12	R00058	D2	C		R00057	X1	C		YC058-YR328
0036	20	PA			1-11	27-53-12	R00058	D3	C		D40610J	3			YC051-YC057
0036	20	PA			2-1	27-53-12	R00058	D3	C		D40610J	3			YC058-YC064
0036	20	PA			2-0	27-53-12	R00058	D3	C		D40610J	3			YC065-YR328
0041	20	PA			1-0	27-53-12	R00057	X2	C		D40610J	14			YC051-YC057
0041	20	PA			1-3	27-53-12	R00057	X2	C		D40610J	14			YC058-YC064

WIRE LIST

D280A108

91-21-11

Section W0090

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0094	286A0094			J4 JUNCTION BOX (continued)											
0041	20		PA		1-2	27-53-12	R00057	X2	C		D40610J	14			YC065-YR328
0042	20		PA		1-0	27-53-12	R00057	D3	C		D40610J	4			YC051-YC057
0042	20		PA		1-3	27-53-12	R00057	D3	C		D40610J	4			YC058-YC064
0042	20		PA		1-2	27-53-12	R00057	D3	C		D40610J	4			YC065-YR328
0052	20		PA		1-9	27-41-12	D40610J	7			R00064	X2	C		YC051-YC058
0052	20		PA		1-9	27-41-12	D40610J	7			R00064	X2	C	*	YC059-YC064
0052	20		PA		2-0	27-41-12	D40610J	7			R00064	X2	C	*	YC065-YR328
0054	20		PA		2-2	27-41-12	D40616J	4			R00064	X2	C	*	YC059-YR328
0071	20		PA		2-7	27-41-12	R00064	X1	C		GD00512	DC..	1A		YC051-YC064
0071	20		PA		2-1	27-41-12	R00064	X1	C		GD00512	DC..	1A		YC065-YD155
0071	20		PA		2-1	22-13-11	R00064	X1	C		D40610J	8			YD157-YR328
0081	20		PA		2-10	33-45-11	D10254	X1			D40610J	2			YL951-YR328
0082	20		PA		2-10	33-45-11	D10254	X2			D40610J	9			YL951-YR328
0083	18		PA		2-10	33-45-11	D10254	A1			D40610J	10			YL951-YR328
0084	18		PA		2-10	33-45-11	D10254	A2			D40610J	11			YL951-YR328
0119	20		PA		3-0	23-32-14	D40612J	13			D11997	7			YD158-YN260
0119	20		PA		3-0	44-21-22	D40612J	13			D11997	7			YN501-YR328
0162	22		PA		1-8	23-32-14	D11997	3			TB0403Y	A003	1A		YD158-YN260
0162	22		PA		1-8	44-21-22	D11997	3			TB0403Y	A003	1A		YN501-YR328
0163	22		PA		2-3	23-32-14	TB0403Y	B003	1A		D40612J	14			YD158-YN260
0163	22		PA		2-3	44-21-22	TB0403Y	B003	1A		D40612J	14			YN501-YR328
0164	22		PA		3-0	23-32-14	D40612J	12			D11997	6			YD158-YN260
0164	22		PA		3-0	44-21-22	D40612J	12			D11997	6			YN501-YR328
0165	20		PA		1-11	23-32-14	D11997	8			GD00512	DC..	1A		YD158-YN260
0165	20		PA		1-11	44-21-22	D11997	8			GD00512	DC..	1A		YN501-YR328
0501	20		PA		2-7	28-23-11	D40658J	1			D13800	X1			YD158
0501	20		PA		0-7	28-23-11	D40658J	1			SM00503		W		YD160-YR328
0502	20		PA		2-7	28-23-11	D40658J	2			D13800	A2			YD158-YR328
0503	20		PA		0-7	28-23-11	D40658J	3			SM00502		W		YD158-YR328
0504	20		PA		2-7	28-23-11	D13800	X2			SM00501		W		YD158-YR328
0505	20		PA		1-2	28-23-11	D13800	A1			D13798	X1			YD158-YR328
0506	20		PA		2-6	28-23-11	D13798	A2			SM00501		W		YD158-YR328
0507	20		PA		2-6	28-23-11	D13798	X2			SM00502		W		YD158-YR328
0508	20		PA		0-7	28-23-11	D40658J	6			SM00502		W		YD158-YR328
0509	20		PA		2-6	28-23-11	D40658J	5			D13798	A3			YD158-YR328
0510	20		PA		0-7	28-23-11	D40658J	4			SM00501		W		YD158-YR328
0511	20		PA		2-7	28-23-11	D13800	X1			SM00503		W		YD160-YR328
0512	20		PA		2-6	28-23-11	D13798	B2			D40658J	7			YD160-YR328
0513	20		PA		2-6	28-23-11	D13798	B3			D40658J	8			YD160-YR328

WIRE LIST

D280A108

91-21-11

Section W0090

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0094		286A0094			J4 JUNCTION BOX (continued)											
0514		20		PA		0-7	28-23-11	D40658J		9		SM00503		W		YD160-YR328
3001B		14		MZ	WA	1-10	27-41-12	D40616J		3		R00064	C2	E		YC051-YC064
3001B		14		MZ	WA	2-1	27-41-12	D40616J		3		R00064	C2	E		YC065-YR328
3001R		14		MZ	WA	0-0	27-41-12	D40616J		1		R00064	A2	E		ALL
3001Y		14		MZ	WA	0-0	27-41-12	D40616J		2		R00064	B2	E		ALL
3003B		14		MZ	WC	2-8	27-41-12	D40602J		4		R00064	C1	E		YC051-YC064
3003B		14		MZ	WC	2-4	27-41-12	D40602J		4		R00064	C1	E		YC065-YR328
3003R		14		MZ	WC	0-0	27-41-12	D40602J		5		R00064	A1	E		ALL
3003Y		14		MZ	WC	0-0	27-41-12	D40602J		6		R00064	B1	E		ALL

WIRE LIST

D280A108

91-21-11

Section W0090

Page 3 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0104	286A0104				P7-CAPTAIN'S GLARESHIELD PANEL (SN2)										
0001	24		PK		2-4	23-51-11	D40738P	19			S01091	1C	Z2		YL951-YR328
0002	24		PK		2-4	23-51-11	D40738P	20			S01091	1NO	Z2		YL951-YR328
1001	20		X1	AA	2-9	31-52-11	L00341	C	\$		D40738P	4			YC051-YD158
1001	20		X1	AA	2-1	31-52-11	D14114	3			D40738P	4			YL951-YR328
1001Z				AA	0-0	31-52-11	D40738P	DED			L00341	DED			YC051-YD158
1001Z				AA	0-0	31-52-11	D14114	DED			D40738P	DED			YL951-YR328
1002	20		X1	AB	2-9	31-52-11	L00341	A	\$		D40738P	6			YC051-YD158
1002	20		X1	AB	2-1	31-52-11	D14114	1			D40738P	6			YL951-YR328
1002Z				AB	0-0	31-52-11	D40738P	DED			L00341	DED			YC051-YD158
1002Z				AB	0-0	31-52-11	D14114	DED			D40738P	DED			YL951-YR328
1003	20		X1	AC	2-9	31-52-11	L00341	B	\$		D40738P	7			YC051-YD158
1003	20		X1	AC	2-1	31-52-11	D14114	2			D40738P	7			YL951-YR328
1003Z				AC	0-0	31-52-11	D40738P	DED			L00341	DED			YC051-YD158
1003Z				AC	0-0	31-52-11	D14114	DED			D40738P	DED			YL951-YR328
1004	20		X1	AD	2-9	31-52-11	L00341	NC	\$		D40738P	5			YC051-YD158
1004	20		X1	AD	2-1	31-52-11	D14114	4			D40738P	5			YL951-YR328
1004Z				AD	0-0	31-52-11	D40738P	DED			L00341	DED			YC051-YD158
1004Z				AD	0-0	31-52-11	D14114	DED			D40738P	DED			YL951-YR328
5501	20		PA		3-4	31-52-11	L00342	7	B		D40738P	1			YC051-YD157
5501	20		PA		3-4	31-52-11	L00342	7	C		D40738P	1			YD158, YL951-YR328
5502	20		PA		3-4	31-52-11	L00342	8	B		D40738P	2			YC051-YD157
5502	20		PA		3-4	31-52-11	L00342	8	C		D40738P	2			YD158, YL951-YR328
5503	20		CQ		3-4	31-52-11	L00342	9	B		D40738P	3			YC051-YD157
5503	20		CQ		3-4	31-52-11	L00342	9	C		D40738P	3			YD158, YL951-YR328
5508	20		CQ		3-4	31-52-25	L00342	1	B		D40738P	8			YC051-YD157
5508	20		CQ		3-4	31-52-25	L00342	1	C		D40738P	8			YD158, YL951-YR328
5509	20		CQ		3-4	31-52-71	L00342	2	B		D40738P	9			YC051-YD157
5509	20		CQ		3-4	31-52-71	L00342	2	C		D40738P	9			YD158, YL951-YR328
5510	20		CQ		3-4	31-52-41	L00342	3	B		D40738P	10			YC051-YD157
5510	20		CQ		3-4	31-52-41	L00342	3	C		D40738P	10			YD158, YL951-YR328
5511	20		CQ		3-4	31-52-31	L00342	4	B		D40738P	11			YC051-YD157
5511	20		CQ		3-4	31-52-31	L00342	4	C		D40738P	11			YD158, YL951-YR328
5512	20		CQ		3-4	31-52-35	L00342	5	B		D40738P	12			YC051-YD157
5512	20		CQ		3-4	31-52-35	L00342	5	C		D40738P	12			YD158, YL951-YR328
5513	20		CQ		3-4	31-52-45	L00342	6	B		D40738P	13			YC051-YD157
5513	20		CQ		3-4	31-52-45	L00342	6	C		D40738P	13			YD158, YL951-YR328
5514R	22		PH		2-9	26-11-21	L00340	NO	\$		D40738P	14			YC051-YD158
5514R	22		PH		2-1	26-11-21	D14118	4			D40738P	14			YL951-YR328
5515R	22		PH		2-9	26-11-21	L00340	C	\$		D40738P	15			YC051-YD158

WIRE LIST

D280A108

91-21-11

Section W0100

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0104		286A0104			P7-CAPTAIN'S GLARESHIELD PANEL (SN2) (continued)											
5515R		22		PH		2-1	26-11-21	D14118		3		D40738P		15		YL951-YR328
5516R		22		PH		2-9	26-11-21	L00340		B	\$	D40738P		16		YC051-YD158
5516R		22		PH		2-1	26-11-21	D14118		2		D40738P		16		YL951-YR328
5517		20		CQ		2-1	33-14-11	D11922		= 1		D40738P		36		YC051-YD158
5517		20		CQ		2-2	33-14-11	D11922		= 1		D40738P		36		YL951-YR328
5518		20		CQ		2-2	33-14-11	D11924		= 1		D40738P		37		YC051-YD158, YL951-YR328
5519		20		CQ		2-9	33-14-11	D11936		= 1		D40738P		38		YC051-YD158, YL951-YR328
5520		20		CQ		2-10	33-14-11	D11938		= 1		D40738P		39		YC051-YD158, YL951-YR328
5521R		20		PH		2-9	33-18-51	L00340		A	\$	D40738P		21		YC051-YD158
5521R		20		PH		2-1	33-18-51	D14118		1		D40738P		21		YL951-YR328
5527		20		CQ		2-5	33-11-31	D40738P		17		L01240	= P	B		YL951-YR328
5528		20		CQ		2-5	33-11-31	D40738P		18		L01240	= G	G		YL951-YR328
A-AA						0-0	31-62-11	T00507		RED		D40738P		22		YC051-YD158, YL951-YR328
A-AB						0-0	31-62-11	T00507		BLU		D40738P		23		YC051-YD158, YL951-YR328
A-AC						0-0	31-62-11	T00507		YEL		D40738P		24		YC051-YD158, YL951-YR328
A-AD						0-0	31-62-11	T00507		BRN		D40738P		25		YC051-YD158, YL951-YR328
A-AE						0-0	31-62-11	T00507		GRN		D40738P		26		YC051-YD158, YL951-YR328
A-AF						0-0	31-62-11	T00507		BLK		D40738P		27		YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0100

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111				E1-1 SHELF										
0001	20		PA		4-2	22-11-11	D41821J	A01			TB1104Y	A001	1A		YC051-YD155
0001	20		PA		4-3	22-11-11	D41821J	A01			D10135C	51			YD157-YR328
0002	20		PA		1-6	22-11-11	D10135C			51	TB1104Y	A001	1A		YC051-YD155
0002	18		PA		4-3	22-11-11	D10135C			55	D41821J	K			YD157-YR328
0003	20		PA		1-6	22-11-11	D10135C			52	TB1104Y	A001	1A		YC051-YD155
0003	20		PA		4-6	22-11-12	D43317J	A06			TB1104Y	A011	1A		YD157-YR328
0004	22		PA		3-1	22-11-11	D10135C	F05			GD01102	AC..	1A		ALL
0005	20		PA		3-1	22-11-11	D10135C			56	GD01102	DC..	1A		ALL
0006	20		PA		3-1	22-11-11	D10135C			57	GD01102	DC..	1A		ALL
0007	20		PA		3-1	22-11-11	D10135C			58	GD01102	DC..	1A		ALL
0008	20		PA		3-1	22-11-11	D10135C			59	GD01102	ST..	1A		ALL
0009	22		PA		4-9	22-11-11	D10135B	H09			D04069J	A02			ALL
0010	22		PA		4-9	22-11-11	D10135B	D01			D04069J	B02			ALL
0011	22		PA		2-7	22-11-11	D10135B	B01			TB1107Y	B005	1A		ALL
0012	22		PA		2-7	22-11-11	D10135B	H01			TB1107Y	A005	1A		ALL
0013	22		PA		2-7	22-11-11	D10135B	F01			TB1107Y	B007	1A		ALL
0014	22		PA		4-7	22-11-11	D04069J	A03			TB1107Y	B005	1A		ALL
0015	22		PA		4-7	22-11-11	D04069J	B03			TB1107Y	A005	1A		ALL
0016	22		PA		4-7	22-11-11	D04069J	A04			TB1107Y	B007	1A		ALL
0018	22		PA		4-0	22-11-11	D10135A	E11			D41121J	A02			ALL
0019	22		PA		4-10	22-11-11	D10135A	B01			D40063J	A04			ALL
001CO				JA	0-0	34-45-21	D02743A	=C1			D04609J	=C1			ALL
001CX			0G	JA	1-7	34-45-21	D02743A	1			D04609J	=A1			ALL
0020	22		PA		4-10	22-11-11	D10135A	H01			D40063J	A05			ALL
0021	22		PA		4-10	22-11-11	D10135A	F01			D40063J	A06			ALL
0022	22		PA		2-9	22-11-11	D02209A			1	D10135C	G05			ALL
0023	20		PA		3-8	22-11-11	D02209A			4	D41811J	A05			ALL
0024	20		PA		2-0	22-11-11	D02209A			6	GD01105	AC..	1A		YC051-YD157
0024	20		PA		3-5	22-11-11	D02209A			6	GD01105	AC..	1A		YD158-YR328
0025	20		PA		2-5	22-11-11	D02209A			31	GD01106	ST..	1A		ALL
0026	20		PA		2-5	22-11-11	D02209A			2	TB1109Z	A017	1A		YC051-YD157
0026	20		PA		3-1	22-11-11	D02209A			2	TB1109Z	A017	1A		YD158-YR328
0027	20		PA		3-9	22-11-11	D41121J	A04			TB1107Y	B005	1A		ALL
0028	20		PA		3-9	22-11-11	D41121J	A05			TB1107Y	A005	1A		ALL
0029	20		PA		3-9	22-11-11	D41121J	A03			TB1107Y	B007	1A		ALL
002CO				JB	0-0	34-45-21	D02743A	=C2			D04611J	=C1			ALL
002CX			0G	JB	1-7	34-45-21	D02743A	2			D04611J	=A1			ALL
0030	20		PA		4-8	22-11-11	D02209B			2	D43317J	B07			ALL
0031	20		PA		3-3	22-11-11	D02209B			7	GD01103	ST..	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0110

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	Wire No.	GA	CO TY		Equip	Term		Type	Splice	Equip	Term	Type	Splice			
W0111	286A0111				E1-1 SHELF (continued)											
0032	20	PA			3-3	22-11-11	D02209B	31				GD01103	DC..	1A		ALL
0033	22	PA			4-8	22-11-11	D02209B	1				D43317J	B08			ALL
0034	20	PA			4-5	22-11-11	D02209B	4				D46013J	A07			ALL
0035	20	PA			3-3	22-11-11	D02209B	6				GD01102	AC..	1A		ALL
0036	20	PA			3-3	22-11-12	D41821J	A03				TB1109Z	B017	1A		YC051-YD157
0036	20	PA			4-7	22-11-12	D41821J	A03				TB1109Z	B017	1A		YD158-YR328
0037	20	PA			1-4	22-11-12	D41821J	A02				SM00263		W		YC051-YD153
0037	20	PA			1-3	22-11-12	D41821J	A02				SM00263		W		YD154-YR328
0038	20	PA			3-8	22-11-12	D04069J	A05				TB1109Z	B017	1A		YC051-YD157
0038	20	PA			5-0	22-11-12	D04069J	A05				TB1109Z	B017	1A		YD158-YR328
0039	20	PA			3-8	22-11-12	D04069J	B05				TB1109Z	B017	1A		YC051-YD157
0039	20	PA			5-0	22-11-12	D04069J	B05				TB1109Z	B017	1A		YD158-YR328
003CO			JC		0-0	34-45-21	D02743A	=C3				D04613J	=C1			ALL
003CX		0G	JC		1-7	34-45-21	D02743A	3				D04613J	=A1			ALL
0040	20	PA			3-3	22-11-12	D04075J	A03				TB1109Z	B017	1A		YC051-YD157
0040	20	PA			4-7	22-11-12	D04075J	A03				TB1109Z	B017	1A		YD158-YR328
0041	20	PA			2-5	22-11-12	D02209A	107				TB1109Z	B017	1A		YC051-YD155
0041	20	PA			2-9	22-11-12	D02209A	107				TB1104Y	A011	1A		YD157
0041	20	PA			3-1	22-11-12	D02209A	107				TB1109Z	B017	1A		YD158-YR328
0042	20	PA			3-4	22-11-12	D04073J	A02				TB1109Z	B017	1A		YC051-YD157
0042	20	PA			4-8	22-11-12	D04073J	A02				TB1109Z	B017	1A		YD158-YR328
0043	20	PA			2-3	22-11-12	D40452J	A01				SM00263		W		ALL
0044	22	PA			4-4	22-11-12	D04075J	A04				D10135B	K07			ALL
0045	22	PA			4-3	22-11-12	D40452J	A02				D10135A	B03			ALL
0046	22	PA			4-2	22-11-12	D40452J	A03				D10135B	J05			ALL
0047	20	PA			4-3	22-11-12	D04073J	A01				TB1107Y	A007	1A		YC051-YD157
0047	20	PA			4-4	22-11-12	D04073J	A01				TB1107Y	A007	1A		YD158-YR328
0048	22	PA			2-7	22-11-12	D10135B	B13				TB1107Y	A007	1A		ALL
0049	20	PA			3-9	22-11-12	D41121J	A06				TB1107Y	A007	1A		ALL
004CO			JD		0-0	34-45-21	D02743A	=C4				D04615J	=C1			ALL
004CX		0G	JD		1-7	34-45-21	D02743A	4				D04615J	=A1			ALL
0050	20	PA			3-10	22-11-12	D41121J	A07				TB1107Y	A003	1A		ALL
0051	22	PA			2-10	22-11-12	D10135A	B13				TB1107Y	A003	1A		ALL
0052	20	PA			4-10	22-11-12	D04079J	A01				TB1107Y	A003	1A		ALL
0053	20	G5			1-7	22-11-12	TB1109Z	A021	1A			TB1109Z	B017	1A		YC051-YD157
0053	20	G5			1-10	22-11-12	TB1109Z	A021	1A			TB1109Z	B017	1A		YD158-YR328
0054	22	G5			3-10	22-11-12	D10135B	F03				TB1109Z	A021	1A		YC051-YD157
0054	22	G5			3-1	22-11-12	D10135B	F03				TB1109Z	A021	1A		YD158-YR328
0055	20	G5			3-11	22-11-12	D04079J	A02				TB1109Z	A021	1A		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0110

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111				E1-1 SHELF (continued)										
0055	20		G5		5-2	22-11-12	D04079J	A02			TB1109Z	A021	1A		YD158-YR328
0056	20		G5		3-4	22-11-12	D41125J	A11			TB1109Z	A021	1A		YC051-YD157
0056	20		G5		4-8	22-11-12	D41125J	A11			TB1109Z	A021	1A		YD158-YR328
0057	22		PA		4-6	22-11-12	D10135A	J10			D41125J	B11			ALL
0058	20		PA		4-8	22-11-12	D43317J	A06			D02209B	107			YC051-YD155
0058	20		PA		2-8	22-11-12	D02209B	107			TB1104Y	A011	1A		YD157-YR328
0059	22		PA		4-7	22-11-12	D43317J	A07			D10135B	K01			ALL
005CO				JE	0-0	34-45-21	D02743B	= C1			D04617J	= C1			ALL
005CX			0F	JE	1-7	34-45-21	D02743B	1			D04617J	= A1			ALL
0060	22		PA		4-9	22-11-12	D43317J	A08			D10135A	K01			ALL
0061	22		PA		3-2	22-11-14	D04075J	A05			TB1110Y	A013	1A		YC051-YD157
0061	22		PA		4-5	22-11-14	D04075J	A05			TB1110Y	A013	1A		YD158-YR328
0062	22		PA		2-8	22-11-14	D04075J	A06			GD01106	DC..	1A		ALL
0063	24		PK		2-9	22-11-14	D45113J	A03			TB1110Y	A013	1A		YC051-YD157
0063	24		PK		4-0	22-11-14	D45113J	A03			TB1110Y	A013	1A		YD158-YR328
0064	22		PA		1-9	22-11-14	D10009A	D05			TB1110Y	A013	1A		YC051-YD155
0065	22		PA		3-10	22-11-14	D10135A	F04			TB1110Y	A013	1A		YC051-YD157
0065	22		PA		3-0	22-11-14	D10135A	F04			TB1110Y	A013	1A		YD158-YR328
0066	20		PA		6-1	34-45-11	D02743C	1			D41811J	A04			ALL
0067	22		PA		1-6	34-45-11	D02743C	7			GD01102	AC..	1A		ALL
0068	22		PA		2-7	34-45-11	D02743C	8			GD01104	DC..	1A		ALL
0069	22		PA		2-7	34-45-11	D02743C	11			GD01104	DC..	1A		ALL
006CO				JF	0-0	34-45-21	D02743B	= C2			D04619J	= C1			ALL
006CX			0F	JF	1-7	34-45-21	D02743B	2			D04619J	= A1			ALL
0070	22		PA		3-3	22-11-14	D10135B	C01			GD01103	DC..	1A		ALL
0072	22		PA		3-11	22-11-18	D45113J	A01			D10135B	G07			ALL
0073	22		PA		2-9	22-11-18	D10135C	K05			D02209A	83			ALL
0075	22		PA		4-9	22-11-18	D40063J	A10			D02209B	83			ALL
0076	20		G5		4-9	22-11-31	D04069J	A06			TB1106Y	B009	1A		YC051-YC052
0077	22		G5		2-9	22-11-31	D10135B	F13			TB1106Y	B009	1A		YC051-YC052
0078	20		G5		4-5	22-11-31	D04073J	B20			TB1106Y	B009	1A		YC051-YC052
0079	22		G5		4-5	22-11-31	D10135B	D13			D04073J	B19			YC051-YC052
007CO				JG	0-0	34-45-21	D02743B	= C3			D04621J	= C1			ALL
007CX			0F	JG	1-7	34-45-21	D02743B	3			D04621J	= A1			ALL
0080	22		PA		3-1	27-32-11	D00728A	C10			D45113J	A20			ALL
0081	22		PA		3-3	22-11-75	D10135B	A01			GD01103	DC..	1A		ALL
008CO				JH	0-0	34-45-21	D02743B	= C4			D04623J	= C1			ALL
008CX			0F	JH	1-7	34-45-21	D02743B	4			D04623J	= A1			ALL
0095	20		PA		3-9	22-13-11	D04075J	A19			TB1108Y	A011	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0110

Page 3

Nov 12/2012

Bundle No.	Part Number			Description			From			To					
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111			E1-1 SHELF (continued)											
0096	20		PA		3-9	22-13-11	D04083J	A05			TB1108Y	A011	1A		ALL
0097	20		PA		3-9	22-13-11	D04075J	A20			TB1108Y	B011	1A		ALL
0098	20		PA		3-9	22-13-11	D04083J	A04			TB1108Y	B011	1A		ALL
0099	20		CQ		4-3	22-14-11	D43317J	B11			TB1108Y	B009	1A		ALL
009CO				Jl	0-0	34-53-31	D10161	= C1			D02743C	= C12			ALL
009CX			0F	Jl	1-3	34-53-31	D10161	= A1			D02743C	12	DN		ALL
0101	24		PK		5-4	22-11-75	D10135A	A08			M01992	1	1A		ALL
0102	24		PK		5-4	22-11-75	D10135A	B08			M01992	2	1A		ALL
0103	24		PK		5-4	22-11-75	D10135A	E07			M01992	3	1A		ALL
0104	24		PK		5-4	22-11-75	D10135A	G08			M01992	4	1A		ALL
0105	24		PK		5-4	22-11-75	D10135A	F08			M01992	5	1A		ALL
0106	24		PK		5-4	22-11-75	D10135A	G07			M01992	6	1A		ALL
0107	24		PK		5-4	22-11-75	D10135A	H06			M01992	7	1A		ALL
0108	24		PK		5-4	22-11-75	D10135A	C08			M01992	8	1A		ALL
0109	24		PK		5-4	22-11-75	D10135A	D08			M01992	9	1A		ALL
0110	24		PK		5-4	22-11-75	D10135A	E08			M01992	10	1A		ALL
0111	24		PK		5-4	22-11-75	D10135A	J07			M01992	11	1A		ALL
0112	24		PK		5-4	22-11-75	D10135A	J08			M01992	12	1A		ALL
0114	24		PK		5-4	22-11-75	D10135A	F07			M01992	14	1A		ALL
0115	24		PK		5-4	22-11-75	D10135A	H08			M01992	15	1A		ALL
0116	22		PA		3-4	22-11-75	D10135A	B07			GD01102	DC..	1A		YC051-YL999, YR301-YR328
0117	22		PA		4-7	27-51-11	D40818J	A01			TB1105Z	B009	1A		ALL
0118	22		PA		3-9	27-51-11	D40818J	B01			GD01102	AC..	1A		ALL
0119	22		G5		3-6	27-81-51	D41125J	B17			D00728A	D12			YC051-YD157
0119	22		G5		3-7	27-81-51	D41125J	B17			D00728A	D12			YD158-YR328
0120	22		G5		3-6	27-81-51	D41125J	B20			D00728A	A11			YC051-YD157
0120	22		G5		3-7	27-81-51	D41125J	B20			D00728A	A11			YD158-YR328
0121	20		G5		2-11	34-61-22	D41821J	B01			D46461J	B11			ALL
0122	20		PA		2-10	34-61-22	D41155J	B09			D00235B	11			ALL
0123	20		PA		2-10	34-61-22	D41155J	B10			D00235B	65			ALL
0124	24		PK		5-5	22-11-75	D10135A	K08			M01992	24	1A		ALL
0125	22		PA		3-7	22-11-75	M01992	25	1A		GD01104	DC..	1A		ALL
0127	22		G5		4-2	27-62-11	D40452J	A10			D10135B	J03			ALL
0128	22		PA		3-2	27-62-11	D40452J	B10			TB1109Z	A021	1A		YC051-YD157
0128	22		PA		4-6	27-62-11	D40452J	B10			TB1109Z	A021	1A		YD158-YR328
0130	20		PA		5-3	22-18-11	D41811J	A06			TB1106Y	B003	1A		ALL
0131	22		PA		2-10	22-18-11	D10135C	A05			TB1106Y	B003	1A		ALL
0132	22		PA		2-10	22-18-11	D10135C	B05			TB1106Y	B003	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0110

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111			E1-1 SHELF (continued)											
0133	22		PA		3-1	22-18-11	D10135C		D05		GD01102	AC..	1A		ALL
0134	22		PA		3-1	22-18-11	D10135C		E05		GD01102	AC..	1A		ALL
0135	20		G5		3-5	22-18-11	D04425J		B03		D02209A	62			ALL
0136	22		PA		3-10	22-18-11	D41155J		B12		D10135C	J03			ALL
0137	20		PA		6-1	22-18-11	D46023J		A03		TB1109Y	B015	1A		YC051-YD157
0137	20		PA		4-9	22-18-11	D46023J		A03		TB1109Y	B015	1A		YD158-YR328
0138	20		PA		6-1	22-18-11	D43317J		B12		TB1109Y	B015	1A		YC051-YD157
0138	20		PA		4-8	22-18-11	D43317J		B12		TB1109Y	B015	1A		YD158-YR328
0139	20		PA		2-3	22-18-11	D02209B		39		TB1109Y	B015	1A		YC051-YD157
0139	20		PA		3-0	22-18-11	D02209B		39		TB1109Y	B015	1A		YD158-YR328
0141	20		PA		3-9	22-13-11	D04075J		B01		TB1108Y	A009	1A		ALL
0142	20		PA		4-6	22-13-11	D40464J		A02		TB1108Y	A009	1A		ALL
0143	22		G5		6-4	23-51-51	D41147J		A09		D46461J	B08			ALL
0144	22		PA		1-7	23-51-51	D45113J		B17		D46461J	A13			ALL
0145	20		PA		1-6	22-13-11	D04075J		B03		D04083J	B03			ALL
0146	20		PA		4-4	22-13-11	D04075J		B02		TB1107Y	B001	1A		ALL
0147	22		PA		2-7	22-13-11	D10135C		B03		TB1107Y	B001	1A		ALL
0148	22		PA		3-10	22-13-11	D41121J		A09		TB1107Y	B001	1A		ALL
0149	20		PA		4-4	22-13-11	D40464J		A01		TB1107Y	A001	1A		ALL
0150	22		PA		2-7	22-13-11	D10135C		D03		TB1107Y	A001	1A		ALL
0151	22		PA		3-10	22-13-11	D41121J		A08		TB1107Y	A001	1A		ALL
0152	20		PA		4-6	22-13-11	D04075J		A10		TB1106Y	A007	1A		ALL
0153	20		PA		4-6	22-13-11	D04075J		A11		TB1106Y	B007	1A		ALL
0154	20		PA		4-4	22-13-11	D04075J		A12		TB1106Y	A009	1A		ALL
0155	22		G5		4-3	22-13-11	D04075J		A13		D10135C	F02			ALL
0156	22		G5		4-3	22-13-11	D04075J		A14		D10135C	B02			ALL
0157	22		PA		6-8	22-13-11	D04075J		A15		D43317J	A15			ALL
0158	22		PA		6-8	22-13-11	D04075J		A16		D43317J	A12			ALL
0159	22		G5		4-8	22-13-11	D40019J		A01		D10135C	D02			ALL
0160	22		PA		2-9	22-13-11	D10135C		K03		TB1106Y	A007	1A		ALL
0161	22		PA		2-9	22-13-11	D10135C		G02		TB1106Y	B007	1A		ALL
0162	22		PA		2-8	22-13-11	D10135C		H03		TB1106Y	A009	1A		ALL
0163	22		G5		3-10	22-13-11	D10135C		H02		D41155J	A16			ALL
0164	22		PA		2-5	22-13-11	D10135C		A03		TB1107Y	A011	1A		ALL
0165	22		PA		2-5	22-13-11	D10135C		J02		TB1107Y	B011	1A		ALL
0166	20		PA		4-0	22-13-11	D41121J		A10		TB1106Y	A007	1A		ALL
0167	20		PA		4-0	22-13-11	D41121J		A11		TB1106Y	B007	1A		ALL
0168	20		PA		3-10	22-13-11	D41121J		A12		TB1106Y	A009	1A		YC051-YD157
0168	20		PA		3-11	22-13-11	D41121J		A12		TB1106Y	A009	1A		YD158-YR328

WIRE LIST

D280A108

91-21-11
Section W0110
Page 5
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111		286A0111			E1-1 SHELF (continued)											
0169		20		PA		3-7	22-13-11	D41121J	A13			TB1107Y	A011	1A		ALL
0170		20		PA		3-7	22-13-11	D41121J	A14			TB1107Y	B011	1A		ALL
0171		20		PA		4-2	22-13-11	D04083J	B04			TB1107Y	A011	1A		ALL
0172		20		PA		3-9	27-31-11	D43211J	A08			TB1107Y	B011	1A		YC051-YD157
0172		20		PA		3-10	27-31-11	D43211J	A08			TB1107Y	B011	1A		YD158-YR328
0173		20		PA		2-3	22-13-11	D02209A	121			TB1108Y	A009	1A		ALL
0174		20		PA		3-9	22-13-11	D04083J	B07			TB1108Y	A009	1A		ALL
0175		20		CQ		4-1	22-14-11	D45203J	B01			TB1108Z	A013	1A		ALL
0176		22		G5		3-4	22-14-11	D04069J	A10			D02209A	47			ALL
0177		22		PA		4-11	22-14-11	D04069J	B10			TB1106Y	A003	1A		ALL
0178		22		PA		1-7	22-14-11	D04069J	A11			D40019J	A03			ALL
0179		20		CQ		2-2	22-14-11	D02209A	48			TB1108Z	A013	1A		ALL
0180		20		CQ		2-2	22-14-11	D10135C	54			TB1108Z	A013	1A		ALL
0181		20		CQ		2-2	22-14-11	D10135C	55			TB1108Z	A013	1A		YC051-YD155
0181		22		PA		4-9	22-14-11	D10135B	J04			D04069J	A14			YD157-YR328
0182		22		CQ		4-0	22-14-11	D40019J	B10			TB1108Z	A013	1A		YC051-YD157
0182		22		CQ		4-1	22-14-11	D40019J	B10			TB1108Z	A013	1A		YD158-YR328
0183		22		PA		5-0	22-14-11	D40019J	A04			TB1106Y	A003	1A		ALL
0184		22		PA		3-1	22-14-11	D10135A	E05			TB1106Y	A003	1A		ALL
0186		22		CQ		3-7	22-14-11	D10135B	B07			TB1109Y	A001	1A		YC051-YD155
0186		22		CQ		4-7	22-14-11	D10135B	B07			D43317J	B10			YD157-YR328
0187		22		CQ		3-7	22-14-11	D40019J	A06			TB1109Y	A015	1A		YC051-YD157
0187		22		CQ		4-11	22-14-11	D40019J	A06			TB1109Y	A015	1A		YD158-YR328
0188		22		PA		4-9	22-14-11	D10135B	G05			D40019J	A05			ALL
0189		22		CQ		3-9	22-14-11	D10135B	D07			TB1109Y	A015	1A		YC051-YD157
0189		22		CQ		2-11	22-14-11	D10135B	D07			TB1109Y	A015	1A		YD158-YR328
0190		20		CQ		4-0	22-14-11	D46013J	A10			TB1108Y	B009	1A		ALL
0191		22		CQ		2-2	22-14-11	D02209B	48			TB1108Y	B009	1A		ALL
0192		22		CQ		2-8	22-14-11	D41121J	A15			TB1109Y	A015	1A		YC051-YD157
0192		22		CQ		4-0	22-14-11	D41121J	A15			TB1109Y	A015	1A		YD158-YR328
0193		22		CQ		3-7	22-14-11	D04069J	B11			TB1109Y	A015	1A		YC051-YD157
0193		22		CQ		4-11	22-14-11	D04069J	B11			TB1109Y	A015	1A		YD158-YR328
0194		22		G5		3-9	22-14-11	D43211J	A15			TB1107Y	B009	1A		YC051-YD157
0194		22		G5		3-10	22-14-11	D43211J	A15			TB1107Y	B009	1A		YD158-YR328
0195		22		G5		2-5	22-14-11	D10135C	K02			TB1107Y	B009	1A		ALL
0196		22		G5		3-7	22-14-11	D41121J	A17			TB1107Y	B009	1A		ALL
0197		22		CQ		5-5	22-14-11	D43317J	B10			TB1109Y	A001	1A		YC051-YD155
0198		22		CQ		1-6	22-14-11	D10009B	D09			TB1109Y	A001	1A		YC051-YD155
0199		20		PA		4-3	22-18-11	D41821J	A04			D10135C	53			ALL

WIRE LIST

D280A108

91-21-11

Section W0110

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111			E1-1 SHELF (continued)											
0201	24		PK		1-6	22-11-75	M01993		1	1A	D41163J	A11			ALL
0202	24		PK		1-6	22-11-75	M01993			1A	D41163J	A12			YC051-YC063
0202	24		PK		1-6	22-11-75	M01993		2	1A	D41163J	A12			YC064-YR328
0203	24		PK		1-6	22-11-75	M01993		3	1A	D41163J	A13			ALL
0204	24		PK		1-6	22-11-75	M01993		4	1A	D41163J	A14			ALL
0205	24		PK		1-6	22-11-75	M01993		5	1A	D41163J	A15			ALL
0206	24		PK		1-6	22-11-75	M01993		6	1A	D41163J	A16			ALL
0207	24		PK		1-6	22-11-75	M01993		7	1A	D41163J	A17			ALL
0208	24		PK		1-6	22-11-75	M01993		8	1A	D41163J	A18			ALL
0209	24		PK		1-6	22-11-75	M01993		9	1A	D41163J	A19			ALL
0210	24		PK		1-6	22-11-75	M01993		10	1A	D41163J	A20			ALL
0211	24		PK		1-6	22-11-75	M01993		11	1A	D41163J	B01			ALL
0212	24		PK		1-6	22-11-75	M01993		12	1A	D41163J	B11			ALL
0214	24		PK		1-6	22-11-75	M01993		14	1A	D41163J	B18			ALL
0215	24		PK		1-6	22-11-75	M01993		15	1A	D41163J	B19			ALL
0216	22		PA		2-8	22-31-11	D10009B	A08			GD01106	DC..	1A		YC051-YD155
0217	22		PA		2-5	27-81-41	D00728B	D02			GD01105	DC..	1A		YC051-YD157
0217	22		PA		3-3	27-81-41	D00728B	D02			GD01105	DC..	1A		YD158-YL952, YN231-YN501
0218	22		PA		3-2	27-81-41	D00728B	H02			GD01102	DC..	1A		ALL
0219	22		PA		3-10	34-21-16	D00235A	69			GD01104	DC..	1A		ALL
0221	20		PA		1-9	22-11-12	D04069J	B04			SM00263		W		YC051-YD153
0221	20		PA		1-8	22-11-12	D04069J	B04			SM00263		W		YD154-YR328
0222	22		PA		3-5	27-32-11	D41821J	A05			SM00069		W		ALL
0223	22		PA		0-7	27-81-11	D00728B	G05			SM00069		W		ALL
0224	24		PK		1-7	22-11-75	M01993	24	1A		D41163J	B20			ALL
0225	22		PA		3-7	22-11-75	M01993	25	1A		GD01104	DC..	1A		ALL
0227	22		PA		5-5	34-45-11	D02743E	F13			D40019J	B11			ALL
0228	24		PK		4-9	34-45-11	D02743E	K05			D40454J	A02			ALL
0229	22		PA		2-8	34-45-11	D02743E	E07			GD01104	DC..	1A		ALL
0230	22		PA		2-8	34-45-11	D02743E	J07			GD01104	DC..	1A		ALL
0231	24		PK		3-9	34-45-11	D02743E	E13			D41157J	B09			ALL
0232	24		PK		4-7	34-45-11	D02743E	C14			D45113J	B02			ALL
0233	22		PA		2-5	34-49-11	D01153C		3		GD01105	AC..	1A		YC051-YD157
0233	22		PA		4-5	34-49-11	D01153C		3		GD01105	AC..	1A		YD158-YR328
0234	22		PA		2-5	34-49-11	D01153C		4		GD01105	DC..	1A		YC051-YD157
0234	22		PA		4-5	34-49-11	D01153C		4		GD01105	DC..	1A		YD158-YR328
0235	24		PK		3-0	34-45-21	D02743F	A07			TB1102Z	A013	1A		YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0110

Page 7

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111				E1-1 SHELF (continued)											
0236	24		PK		3-0	34-45-21		D02743F		C07			TB1102Z	A013	1A	YC051-YD157, YL951-YR328
0237	24		PK		3-0	34-45-21		D02743F		B07	VP		TB1102Z	A013	1A	YC051-YD157
0238	24		PK		3-0	34-45-21		D02743F		E08			TB1102Z	A013	1A	ALL
0239	24		PK		3-0	34-45-21		D02743F		K07			TB1102Z	A013	1A	ALL
0240	22		PA		4-8	22-18-11		D43317J		B13			D02209B		45	ALL
0241	22		PA		4-8	22-18-11		D43317J		B14			D02209B		40	ALL
0242	22		PA		4-8	22-18-11		D43317J		B15			D02209B		46	ALL
0243	22		PA		4-8	22-18-11		D43317J		B16			D02209B		41	ALL
0244	22		PA		4-8	22-18-11		D43317J		B09			D02209B		55	ALL
0245	22		PA		2-9	22-18-11		D10135C		D01			D02209A		45	ALL
0246	22		PA		2-9	22-18-11		D10135C		K01			D02209A		40	ALL
0247	22		PA		2-9	22-18-11		D10135C		C03			D02209A		41	ALL
0248	22		PA		2-9	22-18-11		D10135C		F03			D02209A		46	ALL
0249	22		G5		3-4	22-18-11		D02209A		57			GD01103	DC..	1A	ALL
0250	20		PA		2-9	22-23-11		D41821J		A07			D45113J	B03		ALL
0251	22		PA		3-0	27-32-11		SM00069			W		D45113J	A02		ALL
0252	22		PA		3-1	27-32-11		D45113J		B20			D00728A	D11		ALL
0254	24		PK		3-1	34-45-21		D02743E		H06			TB1102Y	A009	1A	ALL
0255	24		PK		3-1	34-45-21		D02743E		J06			TB1102Y	A009	1A	ALL
0256	24		PK		3-1	34-45-21		D02743E		K06			TB1102Y	A009	1A	ALL
0263	22		PA		3-6	34-49-11		D01153C		2			D41811J	A07		YC051-YD157
0263	22		PA		3-7	34-49-11		D01153C		2			D41811J	A07		YD158-YR328
0264	24		PK		3-4	34-49-11		D01153B		D09			D40019J	A11		YC051-YD157
0264	24		PK		3-6	34-49-11		D01153B		D09			D40019J	A11		YD158-YR328
0265	24		PK		2-11	34-49-11		D01153B		D03			TB1110Y	A015	1A	YC051-YC052
0266	24		PK		3-7	34-49-11		D40019J		A12			TB1110Y	A015	1A	YC051-YD157
0266	24		PK		4-10	34-49-11		D40019J		A12			TB1110Y	A015	1A	YD158-YR328
0267	24		PK		4-3	34-49-11		D02743F		B05			TB1110Y	A015	1A	YC051-YC052
0268	24		PK		3-4	34-49-11		D01153B		C09			D40019J	A13		YC051-YD157
0268	24		PK		3-6	34-49-11		D01153B		C09			D40019J	A13		YD158-YR328
0271	22		PA		3-3	22-11-11		D04075J		B07			TB1109Z	A017	1A	YC051-YD157
0271	22		PA		4-7	22-11-11		D04075J		B07			TB1109Z	A017	1A	YD158-YR328
0272	22		PA		2-8	22-11-11		D04075J		B08			GD01106	AC..	1A	ALL
0273	22		PA		3-3	22-11-11		D04075J		B13			TB1109Z	A017	1A	YC051-YD157
0273	22		PA		4-7	22-11-11		D04075J		B13			TB1109Z	A017	1A	YD158-YR328
0274	22		PA		2-8	22-11-11		D04075J		B14			GD01106	AC..	1A	ALL
0275	22		PA		3-3	22-11-11		D04075J		A01			TB1109Z	A017	1A	YC051-YD157
0275	22		PA		4-7	22-11-11		D04075J		A01			TB1109Z	A017	1A	YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0110

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111			E1-1 SHELF (continued)											
0276	22		PA		2-8	22-11-11	D04075J		A02		GD01106	AC..	1A		ALL
0277	22		PA		3-4	22-11-11	D04073J		A10		TB1109Z	A017	1A		YC051-YD157
0277	22		PA		4-8	22-11-11	D04073J		A10		TB1109Z	A017	1A		YD158-YR328
0278	22		PA		2-8	22-11-11	D04073J		A11		GD01106	AC..	1A		YC051-YD157
0278	22		PA		2-9	22-11-11	D04073J		A11		GD01106	AC..	1A		YD158-YR328
0279	24		PK		3-7	34-49-11	D40019J		A14		TB1110Y	B015	1A		YC051-YD157
0279	24		PK		4-10	34-49-11	D40019J		A14		TB1110Y	B015	1A		YD158-YR328
0280	24		PK		2-11	34-49-11	D01153B		C07		TB1110Y	B015	1A		YC051-YD157
0280	24		PK		4-0	34-49-11	D01153B		C07		TB1110Y	B015	1A		YD158-YR328
0281	24		PK		3-0	34-49-11	D01153A		D12		TB1110Y	B015	1A		YC051-YD157
0281	24		PK		4-1	34-49-11	D01153A		D12		TB1110Y	B015	1A		YD158-YR328
0282	24		PK		3-4	34-49-11	D40019J		A15		D01153B	A09			YC051-YD157
0282	24		PK		3-6	34-49-11	D40019J		A15		D01153B	A09			YD158-YR328
0283	24		PK		3-4	34-49-11	D40019J		A16		D01153B	B09			YC051-YD157
0283	24		PK		3-6	34-49-11	D40019J		A16		D01153B	B09			YD158-YR328
0284	24		PK		4-7	34-49-11	D02743F		C05		D01153B	B07			YC051-YC052
0285	24		PK		2-9	34-49-11	D01153A		A12		D45133J	A01			YC051-YC052
0287	22		PA		2-6	34-49-11	D01153B		D04		GD01105	DC..	1A		YC051-YC052
0288	24		PK		2-7	34-49-11	D40454J		A01		D01153B	A01			YC051-YD157
0288	24		PK		2-9	34-49-11	D40454J		A01		D01153B	A01			YD158-YR328
0289	22		PA		2-6	34-49-11	D01153B		D02		GD01105	DC..	1A		YC051-YC052
0290	22		PA		2-6	34-49-11	D01153B		A05		GD01105	DC..	1A		YC051-YC052
0291	22		PA		2-8	34-49-11	D01153A		A11		GD01105	DC..	1A		YC051-YC052
0292	22		PA		2-8	34-49-11	D01153A		C10		GD01105	DC..	1A		YC051-YC052
0293	22		PA		2-6	34-49-11	D01153B		D14		GD01105	DC..	1A		YC051-YC052
0295	22		PA		2-2	SPARE	D41811J		A09		D41125J	B16			YC051-YC052
0296	22		PA		2-7	22-31-11	D10009C		2		GD01106	DC..	1A		YC051-YD155
0297	18		CQ		6-1	22-31-11	D46023J		H		D10009C		4		YC051-YD155
0298	22		G5		1-5	22-31-11	D10009C		3		GD01105	DC..	1A		YC051-YC052
0298	22		G5		2-7	22-31-11	D10009C		3		GD01106	DC..	1A		YC053-YD155
0299	22		G5		6-2	22-31-11	D10009B		A13		D41163J	B14			YC051-YD155
0300	18		PA		3-2	22-31-11	D41821J		F		D10009C		1		YC051-YD155
0300	18		PA		4-3	22-31-31	D41821J		F		D10135C		52		YD157-YR328
0301	24		PK		4-0	34-49-11	D01153A		B11		M01989		1	1A	YC051-YC052
0302	24		PK		3-10	34-49-11	D01153B		B02		M01989		2	1A	YC051-YC052
0303	24		PK		3-10	34-49-11	D01153B		B08		M01989		3	1A	YC051-YC052
0306	24		PK		3-10	34-49-11	D01153B		C14		M01989		6	1A	YC051-YC052
0307	24		PK		4-0	34-49-11	D01153A		D10		M01989		7	1A	YC051-YC052
0308	24		PK		4-0	34-49-11	D01153A		D11		M01989		8	1A	YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W0110

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111			E1-1 SHELF (continued)											
0309	24		PK		3-10	34-49-11	D01153B		C02		M01989	9	1A		YC051-YC052
0310	24		PK		3-10	34-49-11	D01153B		A04		M01989	10	1A		YC051-YC052
0311	24		PK		3-10	34-49-11	D01153B		C04		M01989	11	1A		YC051-YC052
0312	24		PK		3-10	34-49-11	D01153B		A14		M01989	12	1A		YC051-YC052
0313	24		PK		3-10	34-49-11	D01153B		C08		M01989	13	1A		YC051-YC052
0314	24		PK		3-10	34-49-11	D01153B		B14		M01989	14	1A		YC051-YC052
0315	24		PK		3-10	34-49-11	D01153B		C06		M01989	15	1A		YC051-YC052
0316	24		PK		3-10	34-49-11	D01153B		D06		M01989	16	1A		YC051-YC052
0317	24		PK		3-10	34-49-11	D01153B		A07		M01989	17	1A		YC051-YC052
0318	24		PK		3-10	34-49-11	D01153B		D05		M01989	18	1A		YC051-YC052
0319	24		PK		3-9	34-49-11	D01153B		A02		M01989	19	1A		YC051-YC052
0320	24		PK		3-10	34-49-11	D01153A		A05		M01989	20	1A		YC051-YC052
0321	24		PK		3-9	34-49-11	D01153B		C15		M01989	21	1A		YC051-YC052
0322	24		PK		3-9	34-49-11	D01153B		A15		M01989	22	1A		YC051-YC052
0323	24		PK		3-9	34-49-11	D01153B		A08		M01989	23	1A		YC051-YC052
0324	24		PK		3-9	34-49-11	D01153B		B15		M01989	24	1A		YC051-YC052
0325	24		PK		3-9	34-49-11	D01153B		A03		M01989	25	1A		YC051-YC052
0326	22		G5		1-7	22-31-11	D10009B		C01		GD01105	DC..	1A		YC051-YD155
0327	22		G5		1-7	22-31-11	D10009B		D01		GD01105	DC..	1A		YC051-YD155
0328	22		G5		1-7	22-31-11	D10009B		D12		GD01105	ST..	1A		YC051-YD155
0329	22		PA		2-9	22-31-11	D10009A		C01		GD01106	DC..	1A		YC051-YD155
0330	22		PA		2-9	22-31-11	D10009A		D01		GD01106	DC..	1A		YC051-YD155
0331	22		PA		2-9	22-31-11	D10009A		D12		GD01106	ST..	1A		YC051-YD155
0332	22		PA		3-9	22-31-11	D10009A		A13		D40019J	A08			YC051-YD155
0333	22		PA		2-8	22-31-11	D10009B		A06		GD01106	DC..	1A		YC051-YD155
0334	22		PA		3-5	22-31-51	D04075J		B15		D10009A	A12			YC051-YD155
0334	22		PA		4-6	22-31-51	D04075J		B15		D10135A	J12			YD157-YR328
0335	22		PA		6-2	22-31-51	D41163J		A08		D10009B	A10			YC051-YD155
0335	22		PA		4-8	22-31-51	D41163J		A08		D10135B	F07			YD157-YR328
0336	22		G5		1-6	22-31-51	D10009B		D14		TB1109Y	B003	1A		YC051-YD155
0336	22		G5		3-7	22-31-51	D10135B		E09		TB1109Y	B003	1A		YD157
0336	22		G5		2-10	22-31-51	D10135B		E09		TB1109Y	B003	1A		YD158-YR328
0337	22		G5		6-0	31-31-15	D41163J		A05		TB1109Y	B003	1A		YC051-YD157
0337	22		G5		4-7	31-31-15	D41163J		A05		TB1109Y	B003	1A		YD158-YR328
0338	22		G5		6-0	22-31-51	D41163J		B09		TB1109Y	B003	1A		YC051-YD157
0338	22		G5		4-7	22-31-51	D41163J		B09		TB1109Y	B003	1A		YD158-YR328
0340	22		PA		3-7	22-31-51	D40019J		A09		TB1109Y	B013	1A		YC051-YD157
0340	22		PA		4-11	22-31-51	D40019J		A09		TB1109Y	B013	1A		YD158-YR328
0341	22		PA		1-9	22-31-51	D10009A		D14		TB1109Y	B013	1A		YC051-YD155

WIRE LIST

D280A108

91-21-11

Section W0110

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111			E1-1 SHELF (continued)											
0341	22		PA		3-10	22-31-51	D10135A		C09		TB1109Y	B013	1A		YD157
0341	22		PA		3-0	22-31-51	D10135A		C09		TB1109Y	B013	1A		YD158-YR328
0342	24		PK		2-11	31-31-15	D43211J		B10		TB1109Y	B013	1A		YC051-YD157
0342	24		PK		4-2	31-31-15	D43211J		B10		TB1109Y	B013	1A		YD158-YR328
0343	22		PA		7-1	22-31-51	D41163J		B08		D04069J	A12			YC051-YD157
0343	22		PA		7-2	22-31-51	D41163J		B08		D04069J	A12			YD158-YR328
0344	22		PA		3-9	22-31-51	D04069J		B12		D10009A	A10			YC051-YD155
0344	22		PA		4-10	22-31-51	D04069J		B12		D10135A	K07			YD157-YR328
0345	22		PA		3-9	22-31-51	D04069J		A13		D10009A	B13			YC051-YD155
0345	22		PA		4-10	22-31-51	D04069J		A13		D10135A	D11			YD157-YR328
0350	22		PA		4-0	34-21-16	D40452J		A08		TB1105Y	B001	1A		ALL
0351	22		PA		3-0	34-21-16	D00235A		74		TB1105Y	B001	1A		ALL
0352	22		PA		3-11	34-21-16	D46461J		B17		TB1105Y	B001	1A		ALL
0353	22		CQ		2-11	34-21-16	TB1105W	A005	1		D00235B	15			ALL
0355	22		PA		2-11	34-21-16	D40454J		B03		D00235B	69			ALL
0356	22		G5		4-9	34-21-21	D41157J		A17		D00235B	60			ALL
0357	22		PA		3-0	34-21-16	D46461J		B18		D00235A	118			YC051-YD157
0357	22		PA		3-1	34-21-16	D46461J		B18		D00235A	118			YD158-YR328
0358	22		G5		4-9	34-21-16	D00235B		9		D41157J	B19			ALL
0361	22		PA		3-3	34-61-16	D40019J		A10		D41155J	B04			ALL
0362	22		PA		3-3	34-61-16	D40019J		B01		D41155J	B05			ALL
0364	22		PA		1-7	34-61-17	D41155J		B20		D40454J	A03			ALL
0365	24		PK		4-3	31-31-15	D43211J		B07		TB1106Y	A003	1A		ALL
0369	22		PA		2-11	31-31-17	D43211J		B08		D41125J	B18			ALL
0370	24		PK		5-3	22-31-52	D41157J		B18		TB1109Y	A003	1A		YC051-YD157
0370	24		PK		4-5	22-31-52	D41157J		B18		TB1109Y	A003	1A		YD158-YR328
0371	24		PK		1-6	22-31-52	D10009B		C14		TB1109Y	A003	1A		YC051-YD155
0371	24		PK		3-7	22-31-52	D10135B		G09		TB1109Y	A003	1A		YD157
0371	24		PK		2-10	22-31-52	D10135B		G09		TB1109Y	A003	1A		YD158-YR328
0373	24		PK		5-3	22-31-52	D41157J		A11		TB1109Y	A003	1A		YC051-YD157
0373	24		PK		4-5	22-31-52	D41157J		A11		TB1109Y	A003	1A		YD158-YR328
0374	22		PA		3-1	34-21-11	D00235A		60		D41145J	A05			ALL
0375	22		PA		1-8	34-21-11	D40452J		A04		D41145J	A01			ALL
0376	22		PA		1-5	34-16-11	D41155J		A11		D41121J	B15			ALL
0377	22		PA		4-0	34-21-15	D41121J		A19		D10135A	G01			ALL
0378	22		PA		3-10	34-21-15	D41121J		A20		D10135B	G01			YC051-YD157
0378	22		PA		3-11	34-21-15	D41121J		A20		D10135B	G01			YD158-YR328
0379	22		PA		2-8	34-21-15	D41121J		B14		D00235B	41			YC051-YD157
0379	22		PA		2-9	34-21-15	D41121J		B14		D00235B	41			YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0110

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description		From	To								
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111			E1-1 SHELF (continued)											
0380	22		PA		3-7	34-21-15	D00235B		118		GD01103	DC..	1A		ALL
0381	22		PA		2-11	34-21-15	D43211J		A07		D00235B	100			ALL
0382	22		PA		3-7	34-21-15	D00235B		57		GD01103	DC..	1A		ALL
0383	20		G5		1-8	34-21-21	D46023J		A07		D41157J	A19			YC051-YL999, YR301-YR328 YN231-YN501
0383	20		PA		1-8	34-21-21	D46023J		A07		D41157J	A19			
0384	20		G5		4-5	34-21-21	D46023J		A06		TB1105Y	A003	1A		ALL
0385	20		G5		4-3	34-21-21	D41157J		A20		TB1105Y	A003	1A		ALL
0386	20		G5		3-0	34-21-21	D00235A		52		TB1105Y	A003	1A		ALL
0387	16		CQ		4-2	34-21-21	D46013J		G		TB1105W	A005	1		ALL
0388	20		CQ		3-0	34-21-21	D00235A		78		TB1105W	A005	1		ALL
0389	20		CQ		3-0	34-21-21	D00235A		94		TB1105W	A005	1		ALL
0390	20		CQ		2-8	34-21-21	D00235A		111		TB1108Y	A007	1A		ALL
0391	20		CQ		2-8	34-21-21	D00235A		112		TB1108Y	A007	1A		ALL
0392	20		CQ		4-2	34-21-21	D41157J		B01		TB1108Y	A007	1A		ALL
0394	20		G5		3-6	34-21-21	D00235B		34		GD01102	AC..	1A		ALL
0398	22		PA		1-8	34-51-11	D40452J		B08		D45113J	B01			ALL
0399	20		PA		3-8	34-21-11	D00235A		1		GD01103	DC..	1A		ALL
0401	22		PA		4-6	22-31-11	D10009A		B04		M01994	1	1A		YC051-YD155
0402	22		PA		4-6	22-31-11	D10009A		A04		M01994	2	1A		YC051-YD155
0403	22		PA		4-6	22-31-11	D10009A		A06		M01994	3	1A		YC051-YD155
0404	22		PA		4-6	22-31-11	D10009A		A08		M01994	4	1A		YC051-YD155
0410	22		PA		1-8	34-61-18	D43211J		A06		D40454J	B10			YC051-YC058
0410	22		PA		1-8	31-32-15	D43211J		A06		D40454J	B10			YC059-YR328
0411	22		PA		4-0	27-53-11	D40364J		B07		D00728B	B01			ALL
0412	22		PA		4-4	22-31-11	D10009B		B04		M01994	12	1A		YC051-YD155
0425	22		PA		3-10	22-31-11	M01994		25	1A	GD01105	DC..	1A		YC051-YD155
0426	22		CQ		3-8	34-51-41	D45203J		A01		TB1109Y	A013	1A		YC051-YD157
0426	22		CQ		5-0	34-51-41	D45203J		A01		TB1109Y	A013	1A		YD158-YR328
0427	22		CQ		3-8	34-51-41	D45203J		A02		TB1109Y	A013	1A		YC051-YD157
0427	22		CQ		5-0	34-51-41	D45203J		A02		TB1109Y	A013	1A		YD158-YR328
0428	22		CQ		2-8	34-51-41	D00235A		117		TB1109Y	A013	1A		YC051-YD157
0428	22		CQ		3-4	34-51-41	D00235A		117		TB1109Y	A013	1A		YD158-YR328
0429	22		CQ		3-9	34-51-41	D45203J		A03		D00235A	73			ALL
0430	22		CQ		4-8	34-51-41	D45203J		A04		TB1104Y	A003	1A		ALL
0431	22		CQ		4-8	34-51-41	D45203J		A05		TB1104Y	A003	1A		ALL
0432	22		CQ		1-8	34-51-41	D10135B		K14		TB1104Y	A003	1A		ALL
0433	22		CQ		3-2	34-51-41	D10135B		E07		D00235A	79			YC051-YD157
0433	22		CQ		3-3	34-51-41	D10135B		E07		D00235A	79			YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0110

Page 12

Nov 12/2012



WIRE LIST
D280A108

91-21-11
Section W0110
Page 13
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111		286A0111				E1-1 SHELF (continued)										
0502		24		PK		4-6	34-49-11	D01153A	B10			TB1103Y	A005	1A		YL953-YL999, YR301-YR328
0505		24		PK		6-0	34-49-11	D01153B	B05			TB1103Y	A005	1A		YC053, YC055
0506		24		PK		4-8	34-49-11	D01153A	A10			TB1103Y	A007	1A		YC053-YC064
0506		24		PK		4-8	34-49-11	D01153A	A10			TB1103Z	B009	1A		YC065-YD157
0506		24		PK		4-7	34-49-11	D01153A	A10			TB1103Z	B009	1A		YD158-YL952, YN231-YN501
0506		24		PK		4-6	34-49-11	D01153A	A10			TB1103Y	B005	1A		YL953-YL999
0506		24		PK		4-7	34-49-11	D01153A	A10			TB1103Z	A009	1A		YR301-YR328
0507		24		PK		3-0	34-49-11	D01153A	C10			TB1110Y	A015	1A		YC053-YD157
0507		24		PK		4-1	34-49-11	D01153A	C10			TB1110Y	A015	1A		YD158-YR328
0508		24		PK		2-11	34-49-11	D01153B	D03			TB1110Y	A015	1A		YC053-YD157
0508		24		PK		4-0	34-49-11	D01153B	D03			TB1110Y	A015	1A		YD158-YR328
0509		24		PK		4-8	34-49-11	D01153A	C02			TB1103Y	A005	1A		YC053-YD157
0509		24		PK		4-6	34-49-11	D01153A	C02			TB1103Y	A005	1A		YD158-YD170
0509		24		PK		4-8	34-49-11	D01153A	C02			TB1103Y	A013	1A		YL951-YR328
0510		24		PK		4-6	34-49-11	D01153B	B04			TB1103Y	B005	1A		YC053, YC055
0510		24		PK		4-6	34-49-11	D01153B	B04			TB1103Y	A007	1A		YC054, YC056-YC064
0510		24		PK		4-7	34-49-11	D01153B	B04			TB1103Z	B009	1A		YC065-YD153
0510		24		PK		2-11	34-49-11	D01153B	B04			TB1110Y	A015	1A		YD154-YD157
0510		24		PK		4-0	34-49-11	D01153B	B04			TB1110Y	A015	1A		YD158-YR308, YR312-YR328
0510		24		PK		6-0	34-49-11	D01153B	B04			TB1103Y	A013	1A		YR309
0511		24		PK		4-6	34-49-11	D01153B	D15			TB1103Y	A005	1A		YC053-YD157
0511		24		PK		4-5	34-49-11	D01153B	D15			TB1103Y	A005	1A		YD158-YR328
0512		24		PK		4-6	34-49-11	D01153B	D14			TB1103Y	A007	1A		YC053-YC064
0512		24		PK		4-7	34-49-11	D01153B	D14			TB1103Z	B009	1A		YC065-YD157
0512		24		PK		4-6	34-49-11	D01153B	D14			TB1103Z	B009	1A		YD158-YL999
0512		24		PK		4-5	34-49-11	D01153B	D14			TB1103Y	A007	1A		YN231-YR328
0513		24		PK		4-6	34-49-11	D01153B	D04			TB1103Y	A005	%A		YC053, YC055
0513		24		PK		4-6	34-49-11	D01153B	D04			TB1103Y	A005	1A		YC054, YC056-YD153
0513		24		PK		4-7	34-49-11	D01153B	D04			TB1103Z	B009	1A		YD154-YD157
0513		24		PK		4-6	34-49-11	D01153B	D04			TB1103Z	B009	1A		YD158-YL999
0513		24		PK		4-5	34-49-11	D01153B	D04			TB1103Y	A007	1A		YN231-YR308, YR312-YR328
0513		24		PK		4-5	34-49-11	D01153B	D04			TB1103Z	B009	1A		YR309
0514		24		PK		4-8	34-49-11	D01153A	C12			TB1103Y	A007	1A		YC053-YC064
0514		24		PK		4-8	34-49-11	D01153A	C12			TB1103Z	B009	1A		YC065-YD157
0514		24		PK		4-7	34-49-11	D01153A	C12			TB1103Z	B009	1A		YD158-YL999

WIRE LIST

D280A108

91-21-11

Section W0110

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111				E1-1 SHELF (continued)										
0514	24		PK		4-6	34-49-11	D01153A	C12			TB1103Y	A007	1A		YN231-YR328
0515	24		PK		2-0	34-49-11	TB1103X	A002	1A		TB1103Z	A009	1A		YC053, YC055
0516	24		PK		2-0	34-49-11	TB1103X	B003	1A		TB1103Z	A009	1A		YC053, YC055
0516	24		PK		4-5	34-49-11	D01153B	B05			TB1103Y	A005	1A		YL951-YR328
0525	24		PK		4-6	34-49-11	D01153B	A08			TB1103X	A002	1A		YC053-YD157
0525	24		PK		4-5	34-49-11	D01153B	A08			TB1103X	A002	1A		YD158-YN501
0525	24		PK		4-5	34-49-11	D01153B	A08			TB1103X	B001	1A		YR301-YR328
0526	24		PK		4-7	34-49-11	D01153B	C02			TB1103Z	A009	1A		YC053-YC064
0526	24		PK		4-7	34-49-11	D01153B	C02			TB1103Z	B009	1A		YC065-YD157
0526	24		PK		4-6	34-49-11	D01153B	C02			TB1103Z	B009	1A		YD158-YL999
0526	24		PK		4-5	34-49-11	D01153B	C02			TB1103Y	A007	1A		YN231-YR328
0527	24		PK		4-7	34-49-11	D01153A	D06			TB1103X	B003	1A		YC053-YD153
0527	24		PK		4-7	34-49-11	D01153A	D06			TB1103X	A003	1A		YD154-YD157
0527	24		PK		4-6	34-49-11	D01153A	D06			TB1103X	A003	1A		YD158-YD170
0527	24		PK		4-7	34-49-11	D01153A	D06			TB1103Z	A009	1A		YL951-YL952, YN231-YN501
0527	24		PK		4-6	34-49-11	D01153A	D06			TB1103X	A001	1A		YL953-YL999, YR301-YR328
0528	24		PK		4-7	34-49-11	D01153B	C08			TB1103Z	A009	1A		YC053-YD157
0528	24		PK		4-6	34-49-11	D01153B	C08			TB1103Z	A009	1A		YD158-YN501
0528	24		PK		4-6	34-49-11	D01153B	C08			TB1103Z	B009	1A		YR301-YR328
0529	24		PK		4-7	34-49-11	D01153B	A03			TB1103Z	A009	1A		YC053-YD157
0529	24		PK		4-6	34-49-11	D01153B	A03			TB1103Z	A009	1A		YD158-YN501
0529	24		PK		4-6	34-49-11	D01153B	A03			TB1103Z	B009	1A		YR301-YR328
0530	24		PK		4-6	34-49-11	D01153B	C15			TB1103Y	B005	1A		YC053-YD157
0530	24		PK		4-5	34-49-11	D01153B	C15			TB1103Y	B005	1A		YD158-YL999
0530	24		PK		4-6	34-49-11	D01153B	C15			TB1103Z	B009	1A		YN231-YN501
0530	24		PK		4-6	34-49-11	D01153B	C15			TB1103Z	A009	1A		YR301-YR328
0531	24		PK		4-8	34-49-11	D01153A	B05			TB1103Y	B005	1A		YC053-YD157
0531	24		PK		4-6	34-49-11	D01153A	B05			TB1103Y	B005	1A		YD158-YL999
0531	24		PK		4-7	34-49-11	D01153A	B05			TB1103Z	B009	1A		YN231-YN501
0531	24		PK		4-7	34-49-11	D01153A	B05			TB1103Z	A009	1A		YR301-YR328
0532	24		PK		4-6	34-49-11	D01153B	B07			TB1103Y	B005	1A		YC053-YD157
0532	24		PK		4-5	34-49-11	D01153B	B07			TB1103Y	B005	1A		YD158-YL999
0532	24		PK		4-6	34-49-11	D01153B	B07			TB1103Z	B009	1A		YN231-YN501
0532	24		PK		4-6	34-49-11	D01153B	B07			TB1103Z	A009	1A		YR301-YR328
0533	24		PK		4-6	34-49-11	D01153B	A02			TB1103X	A001	1A		YC053-YD157
0533	24		PK		4-5	34-49-11	D01153B	A02			TB1103X	A001	1A		YD158-YD170
0533	24		PK		4-6	34-49-11	D01153B	A02			TB1103Z	A009	1A		YL951-YN501

WIRE LIST

D280A108

91-21-11

Section W0110

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111			E1-1 SHELF (continued)											
0533	24		PK		4-6	34-49-11	D01153B	A02			TB1103Z	B009	1A		YR301-YR328
0534	24		PK		2-11	34-49-11	D01153A	A12			TB1110Y	A003	1A		YC053-YD157
0534	24		PK		4-0	34-49-11	D01153A	A12			TB1110Y	A003	1A		YD158-YR328
0535	24		PK		4-9	34-49-11	D01153A	D04			TB1103Y	A013	1A		YC053-YD157
0535	24		PK		4-8	34-49-11	D01153A	D04			TB1103Y	A013	1A		YD158-YR328
0554	24		PK		4-10	22-11-53	D41153J	A02			D10135A	C10			YC059-YR328
0557	24		PK		4-10	22-11-53	D41153J	B02			D10135A	C11			YC059-YR328
0558	24		PK		4-10	22-11-53	D41153J	A03			D10135A	B11			YC059-YR328
0559	24		PK		4-10	22-11-53	D41153J	B03			D10135A	A11			YC059-YR328
0561	22		G5		3-0	34-51-41	D00235B	12			TB1104Z	B013	1A		ALL
0562	22		G5		4-4	34-51-41	D41157J	B06			TB1104Z	B013	1A		ALL
0563	22		G5		4-9	34-51-41	D41157J	B16			D00235B	73			ALL
0564	22		G5		4-4	34-51-41	D41157J	B17			TB1104Z	A013	1A		ALL
0565	22		G5		4-7	34-51-41	D41163J	B17			TB1104Z	A013	1A		ALL
0566	22		G5		1-10	34-51-41	D10135A	D01			TB1104Z	A013	1A		ALL
0567	22		G5		4-4	34-51-41	D41157J	A16			TB1104Z	A013	1A		ALL
0568	22		G5		5-0	34-51-41	D41163J	B16			D00235B	79			ALL
0571	20		G5		3-7	34-21-21	D00235B	1			GD01103	DC..	1A		ALL
0572	22		G5		1-9	34-51-41	D41147J	A08			D41163J	B13			ALL
0576	22		PA		2-11	23-43-11	D00235A	114			D41155J	B13			ALL
0577	22		PA		1-10	23-42-11	D40510J	A02			D41125J	B12			YC051-YD157
0577	22		PA		2-10	23-42-11	D41155J	B14			D41125J	B12			YD158-YR328
0578	22		PA		5-2	23-43-11	D00235A	75			D40818J	A10			ALL
0579	16		CQ		1-9	23-12-21	D46023J	J			D41147J	F			ALL
0580	16		CQ		1-9	23-12-21	D46023J	K			D41147J	G			YC051-YD157
0581	22		PA		4-11	31-53-11	D40464J	A03			D00728A	B12			ALL
0582	22		PA		3-4	31-53-11	D40454J	A08			D10064	45			ALL
0583	24		PK		3-6	24-32-11	D40364J	A03			D02209A	79			ALL
0586	24		PK		3-6	24-32-11	D40364J	A08			D02209A	64			ALL
0589	24		G6		4-8	21-51-24	D41163J	B07			D00728A	C11			ALL
0590	22		PA		2-9	30-11-11	D41121J	A16			TB1110Y	B013	1A		YC051-YD157
0590	22		PA		3-11	30-11-11	D41121J	A16			TB1110Y	B013	1A		YD158-YR328
0591	22		PA		2-9	30-11-11	D40122J	B09			TB1110Y	B013	1A		YC051-YD157
0591	22		PA		3-11	30-11-11	D40122J	B09			TB1110Y	B013	1A		YD158-YR328
0592	22		PA		6-2	30-11-11	D40142J	B10			TB1110Y	B013	1A		YC051-YD157
0592	22		PA		4-10	30-11-11	D40142J	B10			TB1110Y	B013	1A		YD158-YR328
0594	22		PA		4-2	78-34-11	D40454J	A10			D10135A	J03			ALL
0597	20		CQ		6-4	26-12-11	D41121J	B19			D40142J	A10			ALL
0598	20		CQ		1-4	26-12-11	D41121J	B20			D40122J	A09			ALL

WIRE LIST

D280A108

91-21-11

Section W0110

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111			E1-1 SHELF (continued)											
0603	24		PK		2-7	27-28-11	D46023J	A02			TB1101Y	B011	1A		ALL
0604	24		PK		2-11	27-28-11	D41563J	A09			TB1101Y	A013	1A		ALL
0605	24		PK		2-9	27-28-11	D40818J	A09			TB1101Y	A013	1A		ALL
0606	24		PK		6-3	27-28-11	D10064	1			TB1101Y	A013	1A		YC051-YD157
0606	24		PK		6-4	27-28-11	D10064	1			TB1101Y	A013	1A		YD158-YR328
0607	24		PK		2-10	27-28-11	D41563J	A08			TB1101Y	B011	1A		ALL
0608	24		PK		2-8	27-28-11	D40818J	A08			TB1101Y	B011	1A		ALL
0610	24		PK		6-2	27-28-11	D10064	41			TB1101Y	B011	1A		ALL
0639	22		PA		4-10	27-53-21	D40162J	A07			TB1105Z	B009	1A		YC051-YD157
0639	22		PA		4-11	27-53-21	D40162J	A07			TB1105Z	B009	1A		YD158-YR328
0641	20		PA		3-10	27-53-11	D40364J	B09			D00728C	8			ALL
0642	20		PA		3-5	27-53-11	TB1102Y	B003	1A		D00728C	3			ALL
0643	20		PA		6-3	27-53-11	D40364J	B10			TB1102Y	B003	1A		ALL
0644	20		PA		4-11	27-53-11	TB1102Y	B003	1A		D43211J	A10			ALL
0645	20		PA		3-0	27-53-11	D00728C	7			D43211J	B14			ALL
0655	22		PA		3-3	27-53-11	D00728B	A02			D40452J	A05			ALL
0659	24		PK		3-0	32-64-21	D10135A	C01			TB1106Y	A005	1A		YC051-YD170, YN231
0660	24		PK		3-11	27-62-21	D40464J	A09			TB1106Y	A005	1A		YC051-YD170, YN231
0665	24		PK		3-11	27-81-12	D40510J	A05			D00728A	D02			ALL
0666	24		PK		3-11	27-81-12	D40510J	B05			D00728A	D01			ALL
0667	24		PK		3-11	27-81-12	D40510J	A06			D00728A	D03			ALL
0668	24		PK		3-11	27-81-12	D40510J	B06			D00728A	C02			ALL
0669	24		PK		3-11	27-81-12	D40510J	A07			D00728A	C01			ALL
0670	24		PK		3-11	27-81-12	D40510J	B07			D00728A	C03			ALL
0671	24		PK		3-11	27-81-12	D40510J	A08			D00728A	B02			ALL
0672	24		PK		3-11	27-81-12	D40510J	B08			D00728A	B01			ALL
0673	24		PK		3-11	27-81-12	D40510J	A09			D00728A	B03			ALL
0674	24		PK		3-11	27-81-12	D40510J	B09			D00728A	A02			ALL
0675	24		PK		3-11	27-81-12	D40510J	A10			D00728A	A01			ALL
0676	24		PK		3-11	27-81-12	D40510J	B10			D00728A	A03			ALL
0677	24		PK		3-11	27-81-21	D40510J	A11			D00728A	A04			ALL
0678	24		PK		3-11	27-81-21	D40510J	B11			D00728A	B05			ALL
0679	24		PK		3-11	27-81-21	D40510J	A12			D00728A	B04			ALL
0680	24		PK		3-11	27-81-21	D40510J	B12			D00728A	A05			ALL
0681	24		PK		3-11	27-81-22	D40510J	A13			D00728A	D08			ALL
0682	24		PK		3-11	27-81-22	D40510J	B13			D00728A	D06			ALL
0683	24		PK		3-11	27-81-22	D40510J	A14			D00728A	D07			ALL
0684	24		PK		3-11	27-81-22	D40510J	B14			D00728A	C08			ALL
0685	24		PK		3-11	27-81-22	D40510J	A15			D00728A	C06			ALL

WIRE LIST

D280A108

91-21-11

Section W0110

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111		286A0111				E1-1 SHELF (continued)									
	0686	24	PK		3-11	27-81-22	D40510J	B15			D00728A	C07			ALL
	0687	24	PK		3-11	27-81-22	D40510J	A16			D00728A	B08			ALL
	0688	24	PK		3-11	27-81-22	D40510J	B16			D00728A	B06			ALL
	0689	24	PK		3-11	27-81-22	D40510J	A17			D00728A	B07			ALL
	0690	24	PK		3-11	27-81-22	D40510J	B17			D00728A	A08			ALL
	0691	24	PK		3-11	27-81-22	D40510J	A18			D00728A	A06			ALL
	0692	24	PK		3-11	27-81-22	D40510J	B18			D00728A	A07			ALL
	0693	24	B6		3-11	27-81-31	D40019J	B05			D00728A	A10			ALL
	0694	24	B6		3-11	27-81-31	D40019J	B06			D00728A	A09			ALL
	0695	24	PK		3-2	27-81-31	D46461J	B05			D00728B	A01			ALL
	0696	22	PA		3-0	27-81-11	D00728C	10			GD01103	ST..	1A		ALL
	0697	22	PA		3-10	27-81-11	D00728C	9			D40364J	A05			ALL
	0699	22	PA		3-3	27-81-11	D00728A	F02			GD01103	DC..	1A		ALL
	0701	22	PA		3-0	27-81-11	D00728C	2			GD01103	DC..	1A		ALL
	0704	22	PA		3-3	27-81-11	D00728A	F01			GD01103	DC..	1A		ALL
	0705	24	PK		3-11	27-81-11	D40510J	A03			D00728A	D04			ALL
	0706	24	PK		3-11	27-81-11	D40510J	B03			D00728A	D05			ALL
	0708	24	PK		3-11	27-81-11	D40510J	A04			D00728A	C05			ALL
	0709	24	PK		3-11	27-81-11	D40510J	B04			D00728A	C04			ALL
	0712	22	PA		5-5	27-53-21	D40162J	B07			GD01102	AC..	1A		ALL
	0713	22	PA		6-0	27-53-21	D40180J	B07			GD01102	AC..	1A		ALL
	0714	22	PA		4-11	27-53-21	D40180J	A07			TB1105Z	A009	1A		ALL
	0715	20	CQ		1-0	34-21-11	SM00101		W		D00235A	47			ALL
	0716	22	PA		2-11	34-61-12	D00235A	92			D41155J	B01			ALL
	0717	22	PA		3-8	34-61-12	D00235A	93			GD01103	DC..	1A		ALL
	0718	22	G5		4-9	34-61-12	D00235B	76			D41157J	B04			ALL
	0719	22	G5		3-7	34-61-12	D00235B	75			GD01103	DC..	1A		ALL
	0720	24	G6		4-3	31-31-15	D41163J	A06			TB1108Y	A011	1A		ALL
	0721	24	G6		4-3	31-31-15	D41163J	B06			TB1108Y	B011	1A		ALL
	0722	22	PA		4-4	22-11-11	D10135B	H14			D41125J	A07			ALL
	0723	22	PA		3-2	27-53-11	D00728B	K01			D43211J	A05			ALL
	0724	16	CQ		3-9	34-21-11	D45203J	F			SM00101		W		ALL
	0725	16	CQ		3-3	34-21-11	D41821J	H			SM00101		W		YC051-YD157
	0725	16	CQ		3-4	34-21-11	D41821J	H			SM00101		W		YD158-YR328
	0726	22	G5		3-5	22-18-11	D04425J	B08			D02209A	61			ALL
	0727	22	G5		3-0	22-18-11	D04425J	B07			GD01106	AC..	1A		ALL
	0728	22	G5		3-0	22-18-11	D04425J	A01			GD01106	AC..	1A		ALL
	0729	22	G5		3-5	22-18-11	D04425J	A02			D02209A	56			ALL
	0731	22	PA		2-6	34-49-11	D45113J	B16			D01153B	D07			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W0110

Page 18

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111			E1-1 SHELF (continued)											
0732	22		PA		4-7	34-49-11	D45133J	B01			D02743F	D05			YC051-YC052
0735	22		PA		4-5	27-81-11	D46023J	A01			D00728C	11			ALL
0736	24		PK		3-2	27-81-31	D00728B	F03			D46461J	A05			ALL
0739	22		CQ		3-11	27-54-11	D40019J	A07			D00728A	D09			ALL
0741	22		PA		3-5	32-31-11	D40019J	A18			D40452J	B03			ALL
0742	22		PA		6-7	32-31-11	D40818J	A05			D40452J	B04			ALL
0745	22		PA		6-7	32-64-11	D40818J	A06			D40452J	A06			ALL
0746	22		PA		4-3	32-64-21	D40452J	B01			TB1106Y	A005	1A		YC051-YD170, YN231
0746	22		PA		4-3	32-64-21	D40452J	B01			D10135A	C01			YL951-YL999, YN232-YR328
0755	22		PA		4-7	22-11-11	D10135B	E11			D43317J	A05			ALL
0756	22		G5		3-6	27-54-11	D00728A	A12			D41125J	B19			YC051-YD157
0756	22		G5		3-7	27-54-11	D00728A	A12			D41125J	B19			YD158-YR328
0761	24		PK		6-1	22-11-75	M02539	1	1A		D10135A	D14			YD157-YR328
0762	24		PK		6-1	22-11-75	M02539	2	1A		D10135A	E14			YD157-YR328
0763	24		PK		6-1	22-11-75	M02539	3	1A		D10135A	F14			YD157-YR328
0765	24		PK		6-1	22-11-75	M02539	5	1A		D10135A	F15			YD157-YR328
0766	24		PK		6-1	22-11-75	M02539	6	1A		D10135A	C13			YD157-YR328
0767	24		PK		6-1	22-11-75	M02539	7	1A		D10135A	E13			YD157-YR328
0768	24		PK		6-0	22-11-75	M02539	8	1A		D10135B	C13			YD157-YR328
0769	24		PK		5-5	22-11-75	M02539	9	1A		D10135B	F15			YD157-YR328
0770	24		PK		5-5	22-11-75	M02539	10	1A		D10135B	E13			YD157-YR328
0771	24		PK		5-5	22-11-75	M02539	11	1A		D10135B	G14			YD157-YR328
0772	24		PK		5-3	22-11-75	M02539	12	1A		D10135C	E01			YD157
0772	24		PK		5-4	22-11-75	M02539	12	1A		D10135C	E01			YD158-YR328
0773	24		PK		5-5	22-11-75	M02539	13	1A		D10135B	E14			YD157-YR328
0774	24		PK		5-5	22-11-75	M02539	14	1A		D10135B	F14			YD157-YR328
0777	22		PA		3-9	22-31-51	D10135B	F10			GD01106	DC..	1A		YD157-YR328
0778	22		CQ		4-0	22-14-11	D40019J	A08			TB1108Z	A013	1A		YD157
0778	22		CQ		4-1	22-14-11	D40019J	A08			TB1108Z	A013	1A		YD158-YR328
0786	24		PK		2-3	22-11-75	M02539	15	1A		D04069J	A15			YD157-YR328
0787	24		PK		5-5	22-11-75	M02539	17	1A		D10135B	C14			YD157-YR328
0788	24		PK		5-5	22-11-75	M02539	18	1A		D10135B	C15			YD157-YR328
0789	24		PK		5-4	22-11-75	M02539	19	1A		D10135B	D14			YD157-YR328
0790	24		PK		6-5	22-11-75	M02539	25	1A		GD01104	DC..	1A		YD157
0790	24		PK		6-6	22-11-75	M02539	25	1A		GD01104	DC..	1A		YD158-YR328
0796	20		PA		2-7	21-31-23	D10740C	2			GD01106	DC..	1A		YD158-YR328
0797	20		PA		2-7	21-31-23	D10740C	4			GD01106	ST..	1A		YD158-YR328
0798	22		PA		2-8	21-31-23	D10740B	C11			GD01106	DC..	1A		YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0110

Page 19

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY	Fam FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W0111	286A0111	E1-1 SHELF (continued)			
0799	22 PA	2-8 21-31-23	D10740B C15	GD01106 DC.. 1A	YD158-YR328
0801	22 G5	3-4 27-83-11	D40364J B08	D45113J B19	ALL
0802	24 PK	6-3 21-31-23	D40064J A08	D10740B B07	YD158-YR328
0803	24 PK	4-1 21-31-23	D40774J A09	D10740A A11	YD158-YR328
0804	24 PK	3-11 21-31-23	D40364J A10	D10740A A13	YD158-YR328
0805	24 PK	3-7 21-31-11	D40510J B19	D10740B B03	YD158-YR328
0806	24 PK	6-5 21-31-23	D40464J B08	D10740B B10	YD158-YR328
0807	24 PK	6-5 21-31-23	D40464J B09	D10740B D07	YD158-YR328
0808	20 PA	6-2 21-31-23	D40464J B10	TB1111Y B009 1A	YD158-YR328
0809	24 B6	2-9 21-51-11	D46461J A06	TB1111Y B011 1A	YD158-YR328
0810	24 B6	6-2 21-51-21	D41563J A02	TB1111Y A011 1A	YD158-YR328
0811	22 PA	2-8 21-31-23	D10740B D08	GD01106 DC.. 1A	YD158-YR328
0814	22 CQ	3-11 34-51-41	D41121J B01	TB1104Y B017 1A	YL951-YR328
0815	22 CQ	4-10 34-51-41	D45203J B04	TB1104Y B017 1A	YL951-YR328
0816	22 CQ	1-10 34-51-41	D10135B C02	TB1104Y B017 1A	YL951-YR328
0817	22 G5	4-9 34-51-41	D41163J A09	D10135A C02	YL951-YR328
0838	22 PA	3-3 27-81-41	D00728B G02	GD01105 DC.. 1A	YL953-YL999, YR301-YR328
0841	22 PA	1-8 23-32-21	D40510J A20	D45203J A09	YL951-YL967, YN231-YN235
0842	22 PA	1-8 23-32-21	D40510J B20	D45203J B09	YL951-YL967, YN231-YN235
0849	22 PA	2-8 34-49-11	D01153A B10	GD01105 DC.. 1A	YC051-YC052
0850	24 PK	4-0 21-31-24	D40774J A03	D10740B B02	YD158-YR328
0851	24 PK	4-0 21-31-24	D40774J B03	D10740B B06	YD158-YR328
0852	24 B6	3-9 21-31-24	D40774J B10	TB1111Y A011 1A	YD158-YR328
0853	24 B6	1-9 21-31-24	D10740B B13	TB1111Y A011 1A	YD158-YR328
0854	24 B6	3-9 21-31-24	D40774J B01	TB1111Y B011 1A	YD158-YR328
0855	24 B6	1-9 21-31-24	D10740B B12	TB1111Y B011 1A	YD158-YR328
0856	24 PK	4-1 21-31-24	D40774J A04	D10740A D03	YD158-YR328
0857	24 PK	4-1 21-31-24	D40774J B04	D10740A A15	YD158-YR328
0858	24 PK	4-0 21-31-24	D40774J A10	D10740B B04	YD158-YR328
0859	24 G6	4-0 21-31-24	D40774J A01	D10740B B01	YD158-YR328
0860	24 PK	1-9 21-31-24	D10740B B09	TB1111Y A009 1A	YD158-YR328
0861	24 PK	3-9 21-31-24	D40774J A02	TB1111Y A009 1A	YD158-YR328
0862	24 PK	3-0 21-31-24	D41125J A17	TB1111Y A009 1A	YD158-YR328
0863	24 PK	5-4 21-31-23	D40160J A10	D10740B B05	YD158-YR328
0865	20 PA	3-6 21-31-23	D40364J A09	TB1111Y B009 1A	YD158-YR328
0866	20 PA	1-8 21-31-23	D10740C 3	TB1111Y B009 1A	YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0110

Page 20

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111				E1-1 SHELF (continued)										
0867	20		PA		5-1	21-31-23	D40160J	A09			TB1111Y	B009	1A		YD158-YR328
0880	24		PK		4-11	34-49-11	D01153A	B12			TB1102Y	A003	1A		YL956-YL999, YN236-YR328
0881	24		PK		3-7	34-49-11	D40133J	A07			D01153A	CAP	Y		YL956-YL999, YN236-YR328
0882	24		PK		3-7	34-49-11	D40133J	B03			D01153A	CAP	Y		YL956-YL999, YN236-YR328
0884	22		CQ		5-6	31-53-11	D40458J	B02			D00235A	34			YC060-YC064
0884	22		CQ		3-0	31-53-11	D40458J	B02			D00235A	34			YL953-YL999, YN233-YR328
0885	22		CQ		5-6	31-53-11	D40458J	B03			D00235A	121			YC060-YC064
0885	22		CQ		3-0	31-53-11	D40458J	B03			D00235A	121			YL953-YL999, YN233-YR328
0886	22		CQ		5-6	31-53-11	D40458J	B04			D00235A	36			YC060-YC064
0886	22		CQ		3-0	31-53-11	D40458J	B04			D00235A	36			YL953-YL999, YN233-YR328
0887	22		CQ		6-6	31-53-11	D46013J	B10			D00235A	57			YC060-YC064
0887	22		CQ		4-10	31-53-11	D46013J	B10			D00235A	57			YL953-YL999, YN233-YR328
0888	20		CQ		5-6	31-53-11	D00235A	44			GD01104	DC..	1A		YC060-YC064
0888	20		CQ		3-10	31-53-11	D00235A	44			GD01104	DC..	1A		YL953-YL999, YN233-YR328
0889	20		CQ		5-6	31-53-11	D00235A	62			GD01104	DC..	1A		YC060-YC064
0889	20		CQ		3-9	31-53-11	D00235A	62			GD01105	DC..	1A		YL953-YL999, YN233-YR328
0890	22		PA		7-6	25-51-21	D40364J	A01			D40464J	B04			YC051-YD170
0890	22		PA		7-6	25-51-21	D40464J	B04			D40364J	A01			YL951-YL999, YR301-YR328
0908	24		PK		3-8	22-11-75	M02540	1	1A		D45515J	A01			YD157-YR328
0909	24		PK		3-8	22-11-75	M02540	2	1A		D45515J	A02			YD157-YR328
0910	24		PK		3-8	22-11-75	M02540	3	1A		D45515J	A03			YD157-YR328
0911	24		PK		3-8	22-11-75	M02540	4	1A		D45515J	A04			YD157-YR328
0912	24		PK		3-8	22-11-75	M02540	5	1A		D45515J	A05			YD157-YR328
0913	24		PK		3-8	22-11-75	M02540	6	1A		D45515J	A06			YD157-YR328
0914	24		PK		3-8	22-11-75	M02540	7	1A		D45515J	A07			YD157-YR328
0915	24		PK		3-8	22-11-75	M02540	8	1A		D45515J	A08			YD157-YR328
0916	24		PK		3-7	22-11-75	M02540	9	1A		D45515J	A09			YD157-YR328
0917	24		PK		3-7	22-11-75	M02540	10	1A		D45515J	A10			YD157-YR328
0918	24		PK		3-7	22-11-75	M02540	11	1A		D45515J	A11			YD157-YR328

WIRE LIST

D280A108

91-21-11

Section W0110

Page 21

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111		286A0111					E1-1 SHELF (continued)									
0919		24		PK		3-7	22-11-75	M02540	12	1A		D45515J	A12			YD157-YR328
0920		24		PK		3-7	22-11-75	M02540	13	1A		D45515J	B01			YD157-YR328
0921		24		PK		3-7	22-11-75	M02540	14	1A		D45515J	B02			YD157-YR328
0922		24		PK		3-7	22-11-75	M02540	15	1A		D45515J	B07			YD157-YR328
0923		24		PK		3-7	22-11-75	M02540	17	1A		D45515J	B03			YD157-YR328
0924		24		PK		3-7	22-11-75	M02540	18	1A		D45515J	B04			YD157-YR328
0925		24		PK		3-6	22-11-75	M02540	19	1A		D45515J	B05			YD157-YR328
0926		24		PK		3-6	22-11-75	M02540	24	1A		D45515J	B06			YD157-YR328
0927		24		PK		6-3	22-11-75	M02540	25	1A		GD01104	DC..	1A		YD157-YR328
1001		22		X1	A	3-10	22-11-11	D10135B	H11			D41121J	A01			YC051-YD157
1001		22		X1	A	3-11	22-11-11	D10135B	H11			D41121J	A01			YD158-YR328
1001Z					A	0-0	22-11-11	D10135B	DED			D41121J	PERG	1F		YC051-YC052
1001Z					A	0-0	22-11-11	GB01104	ST..	1A		D41121J	PERG	1F		YC053-YR328
1002		22		X1	B	4-9	22-11-11	D10135A	H11			D43317J	A04			ALL
1002Z					B	0-0	22-11-11	D10135A	DED			D43317J	PERG	1F		YC051-YC052
1002Z					B	0-0	22-11-11	GB01104	ST..	1A		D43317J	PERG	1F		YC053-YR328
1003		20		X1	C	3-1	27-52-11	TB1105Z	A013	1A		GD01102	AC..	1A		ALL
1003Z					C	0-0	27-52-11	TB1105Z	B013	1A		GD01102	DED			ALL
1004		24		Y1	D	4-3	27-52-11	D46013J	A03			TB1105Z	A009	1A		ALL
1004Z					D	0-0	27-52-11	D46013J	DED			TB1105Z	B013	1A		ALL
1005		24		Y1	E	4-3	27-52-11	D46013J	A04			TB1105Z	B009	1A		ALL
1005Z					E	0-0	27-52-11	D46013J	DED			TB1105Z	B013	1A		ALL
1006		24		Y1	F	2-7	27-52-11	D00728B	E11			TB1105Z	A009	1A		ALL
1006Z					F	0-0	27-52-11	D00728B	DED			TB1105Z	B013	1A		ALL
1007		24		Y1	G	2-7	27-52-11	D00728B	G11			TB1105Z	B009	1A		ALL
1007Z					G	0-0	27-52-11	D00728B	DED			TB1105Z	B013	1A		ALL
1012		20		X1	L	4-10	22-12-31	D04079J	A06			TB1107Y	B003	1A		ALL
1012Z					L	0-0	22-12-31	D04079J	PERG	1F		GB01107	ST..	1A		ALL
1013		20		X1	M	4-8	22-12-31	D04069J	B06			TB1107Y	B003	1A		ALL
1013Z					M	0-0	22-12-31	D04069J	DED			GB01107	ST..	1A		YC051-YC070
1013Z					M	0-0	22-12-31	D04069J	PERG	1F		GB01107	ST..	1A		YD151-YR328
1014		22		X1	N	5-0	22-12-31	D10135A	D13			D04079J	A05			ALL
1014Z					N	0-0	22-12-31	D10135A	DED			D04079J	PERG	1F		YC051-YC052
1014Z					N	0-0	22-12-31	GB01104	ST..	1A		D04079J	PERG	1F		YC053-YR328
1015		22		X1	O	2-10	22-12-31	D10135A	F13			TB1107Y	B003	1A		ALL
1015Z					O	0-0	22-12-31	D10135A	DED			GB01107	ST..	1A		YC051-YC052, YL951-YR328
1015Z					O	0-0	22-12-31	GB01104	ST..	1A		GB01107	ST..	1A		YC053-YD158
1017		20		X1	Q	4-9	22-11-31	D04069J	A06			TB1106Y	B009	1A		YC053-YR328

WIRE LIST

D280A108

91-21-11

Section W0110

Page 22

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111				E1-1 SHELF (continued)										
1017Z				Q	0-0	22-11-31	D04069J	PERG	1F		GB01106	ST..	1A		YC053-YR328
1018	22	X1		R	2-9	22-11-31	D10135B	F13			TB1106Y	B009	1A		YC053-YR328
1018Z				R	0-0	22-11-31	GB01104	ST..	1A		GB01106	ST..	1A		YC053-YD158
1018Z				R	0-0	22-11-31	D10135B	DED			GB01106	ST..	1A		YL951-YR328
1019	20	X1		S	4-5	22-11-31	D04073J	B20			TB1106Y	B009	1A		YC053-YR328
1019Z				S	0-0	22-11-31	D04073J	PERG	1F		GB01106	ST..	1A		YC053-YR328
1021	22	X1		U	4-5	22-11-31	D10135B	D13			D04073J	B19			YC053-YR328
1021Z				U	0-0	22-11-31	GB01104	ST..	1A		D04073J	PERG	1F		YC053-YD158
1021Z				U	0-0	22-11-31	GB01105	ST..	1A		D04073J	PERG	1F		YL951-YR328
1029	20	X1		V	2-9	27-25-11	D41563J	A02			TB1102Y	B009	1A		YD154-YD155
1029Z				V	0-0	27-25-11	D41563J	PERG	1F		GB01102	ST..	1A		YD154-YD155
1031	22	X1		W	3-10	27-25-11	D00728A	C12			TB1102Y	B009	1A		YD154-YD155
1031Z				W	0-0	27-25-11	D00728A	PERG	1A		GB01102	ST..	1A		YD154-YD155
1032	20	N1		H	7-0	27-25-11	D40364J	B01			TB1102Y	A007	1A		YC051-YD153
1032	20	X1		H	6-4	27-25-11	D40364J	B01			TB1102Y	A007	1A		YD154-YR328
1032Z				H	0-0	27-25-11	D40364J	PERG	1F		GB01102	ST..	1A		ALL
1033	22	N1		I	4-0	27-25-11	TB1102Y	B007	1A		D00728A	C12			YC051-YD153
1033	20	X1		I	1-2	27-25-11	TB1102Y	B007	1A		TB1102Y	B009	1A		YD154-YD155
1033	22	X1		I	3-9	27-25-11	D00728A	C12			TB1102Y	B007	1A		YD157-YR328
1033Z				I	0-0	27-25-11	GB01102	ST..	1A		D00728A	PERG	1F		YC051-YD153
1033Z				I	0-0	27-25-11	GB01102	ST..	1A		GB01102	ST..	1A		YD154-YD155
1033Z				I	0-0	27-25-11	D00728A	PERG	1A		GB01102	ST..	1A		YD157-YR328
1035	20	N1		J	7-0	27-25-11	D40364J	A02			TB1102Y	A005	1A		YC051-YD153
1035	20	X1		J	6-4	27-25-11	D40364J	A02			TB1102Y	A005	1A		YD154-YR328
1035Z				J	0-0	27-25-11	D40364J	PERG	1F		GB01102	ST..	1A		ALL
1036	20	N1		K	2-0	27-25-11	TB1102Y	B005	1A		TB1102Y	B007	1A		YC051-YD153
1036	20	X1		K	0-7	27-25-11	TB1102Y	B005	1A		TB1102Y	B007	1A		YD154-YR328
1036Z				K	0-0	27-25-11	GB01102	ST..	1A		GB01102	ST..	1A		ALL
1037	22	X1		GH	5-0	22-11-81	D10135B	K09			D45551J	K			YD157-YR328
1037Z				GH	0-0	22-11-81	GB01104	ST..	1A		D45551J	PERG	1F		YD157-YD158
1037Z				GH	0-0	22-11-81	GB01105	ST..	1A		D45551J	PERG	1F		YL951-YR328
1038	22	X1		GL	5-1	22-11-81	D10135A	K09			D45551J	J			YD157-YR328
1038Z				GL	0-0	22-11-81	GB01104	ST..	1A		D45551J	PERG	1F		YD157-YR328
1041	22	X1		GV	6-4	21-31-23	D40064J	B05			D10740A	D15			YD158-YR328
1041Z				GV	0-0	21-31-23	D40064J	PERG	1F		D10740A	PERG	1A		YD158-YR328
2001B	22	PB		AA	4-10	22-11-11	D10135A	H14			D04069J	B01			ALL
2001R	22	PB		AA	0-0	22-11-11	D10135A	K14			D04069J	A01			ALL
2002B	24	Y2		AB	6-2	34-33-21	D10009B	B03			D41163J	B02			YC051-YD155
2002B	24	Y2		AB	4-8	34-33-21	D10135B	J11			D41163J	B02			YD157-YR328

WIRE LIST

D280A108

91-21-11

Section W0110

Page 23

Nov 12/2012

Bundle No.	Part Number			Description	From			To							
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111			E1-1 SHELF (continued)											
2002R	24		Y2	AB	0-0	34-33-21	D10009B	A03			D41163J	A02			YC051-YD155
2002R	24		Y2	AB	0-0	34-33-21	D10135B	K11			D41163J	A02			YD157-YR328
2002Z				AB	0-0	34-33-21	GB01110	ST..	1A		D41163J	PERG	1F		YC051-YD155
2002Z				AB	0-0	34-33-21	GB01104	ST..	1A		D41163J	PERG	1F		YD157-YR328
2003B	24		Y2	AC	4-11	34-33-21	D01153A	B08			TB1101Y	B001	1A		YC051-YD157
2003B	24		Y2	AC	4-10	34-33-21	D01153A	B08			TB1101Y	B001	1A		YD158-YR328
2003R	24		Y2	AC	0-0	34-33-21	D01153A	A08			TB1101Y	A001	1A		ALL
2003Z				AC	0-0	34-33-21	D01153A	PERG	1A		GB01101	ST..	1A		ALL
2004B	24		Y2	AD	2-8	34-33-21	D02743F	E03			TB1101Y	B001	1A		ALL
2004R	24		Y2	AD	0-0	34-33-21	D02743F	D03			TB1101Y	A001	1A		ALL
2004Z				AD	0-0	34-33-21	D02743F	DED			GB01101	ST..	1A		ALL
2005B	24		Y2	AE	2-5	34-33-21	D41163J	B03			TB1101Y	B001	1A		ALL
2005R	24		Y2	AE	0-0	34-33-21	D41163J	A03			TB1101Y	A001	1A		ALL
2005Z				AE	0-0	34-33-21	D41163J	PERG	1F		GB01101	ST..	1A		ALL
2006B	22		X2	AF	4-4	22-11-31	D04075J	B12			D10135B	J06			ALL
2006R	22		X2	AF	0-0	22-11-31	D04075J	B11			D10135B	K06			ALL
2006Z				AF	0-0	22-11-31	D04075J	PERG	1F		D10135B	DED			YC051-YC052
2006Z				AF	0-0	22-11-31	D04075J	PERG	1F		GB01104	ST..	1A		YC053-YD158
2006Z				AF	0-0	22-11-31	D04075J	PERG	1F		GB01105	ST..	1A		YL951-YR328
2007B	22		X2	AG	4-5	22-11-31	D10135B	A12			D04073J	B05			ALL
2007R	22		X2	AG	0-0	22-11-31	D10135B	B12			D04073J	B04			ALL
2007Z				AG	0-0	22-11-31	D10135B	DED			D04073J	PERG	1F		YC051-YC052
2007Z				AG	0-0	22-11-31	GB01104	ST..	1A		D04073J	PERG	1F		YC053-YD158
2007Z				AG	0-0	22-11-31	GB01105	ST..	1A		D04073J	PERG	1F		YL951-YR328
2008B	22		X2	AH	2-5	22-11-31	D10135B	A15			TB1107Y	B015	1A		ALL
2008R	22		X2	AH	0-0	22-11-31	D10135B	B15			TB1107Y	A015	1A		ALL
2008Z				AH	0-0	22-11-31	D10135B	DED			TB1107Y	DED			YC051-YC052
2008Z				AH	0-0	22-11-31	GB01104	ST..	1A		TB1107Y	DED			YC053-YC070
2008Z				AH	0-0	22-11-31	GB01104	ST..	1A		GB01107	ST..	1A		YD151-YD158
2008Z				AH	0-0	22-11-31	D10135B	DED			GB01107	ST..	1A		YL951-YR328
2009B	22		X2	AI	4-1	22-11-31	D04073J	A05			TB1107Y	B015	1A		ALL
2009R	22		X2	AI	0-0	22-11-31	D04073J	A04			TB1107Y	A015	1A		ALL
2009Z				AI	0-0	22-11-31	D04073J	PERG	1F		TB1107Y	DED			YC051-YC052
2009Z				AI	0-0	22-11-31	D04073J	PERG	1F		GB01107	ST..	1A		YC053-YR328
2010B	22		X2	AK	4-1	22-11-31	D04073J	A07			TB1107Y	B015	1A		ALL
2010R	22		X2	AK	0-0	22-11-31	D04073J	A06			TB1107Y	A015	1A		ALL
2010Z				AK	0-0	22-11-31	D04073J	PERG	1F		TB1107Y	DED			YC051-YC052
2010Z				AK	0-0	22-11-31	D04073J	PERG	1F		GB01107	ST..	1A		YC053-YR328
2011B	22		X2	AL	4-1	22-11-31	D04073J	B13			TB1107Y	B015	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0110

Page 24

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111					E1-1 SHELF (continued)									
2011R	22	X2	AL		0-0	22-11-31	D04073J	B12			TB1107Y	A015	1A		ALL
2011Z			AL		0-0	22-11-31	D04073J	DED			TB1107Y	DED			YC051-YC070
2011Z			AL		0-0	22-11-31	D04073J	PERG	1F		GB01107	ST..	1A		YD151-YR328
2012B	22	X2	AM		4-5	22-11-31	D10135B	D12			D04073J	B08			ALL
2012R	22	X2	AM		0-0	22-11-31	D10135B	E12			D04073J	B07			ALL
2012Z			AM		0-0	22-11-31	D10135B	DED			D04073J	PERG	1F		YC051-YC052
2012Z			AM		0-0	22-11-31	GB01104	ST..	1A		D04073J	PERG	1F		YC053-YD158
2012Z			AM		0-0	22-11-31	GB01105	ST..	1A		D04073J	PERG	1F		YL951-YR328
2013B	22	X2	AN		4-5	22-11-31	D10135B	D15			D04073J	A09			ALL
2013R	22	X2	AN		0-0	22-11-31	D10135B	E15			D04073J	A08			ALL
2013Z			AN		0-0	22-11-31	D10135B	DED			D04073J	PERG	1F		YC051-YC052
2013Z			AN		0-0	22-11-31	GB01104	ST..	1A		D04073J	PERG	1F		YC053-YD158
2013Z			AN		0-0	22-11-31	GB01105	ST..	1A		D04073J	PERG	1F		YL951-YR328
2014B	22	X2	AO		4-7	22-11-31	D10135B	F11			D43317J	A11			YC051-YD155
2014R	22	X2	AO		0-0	22-11-31	D10135B	G11			D43317J	A10			YC051-YD155
2014Z			AO		0-0	22-11-31	GB01104	ST..	1A		D43317J	PERG	1F		YC051-YD155
2015B	24	Y2	AP		4-8	22-11-51	D04069J	B08			TB1106Z	B013	1A		ALL
2015R	24	Y2	AP		0-0	22-11-51	D04069J	A08			TB1106Z	A013	1A		ALL
2015Z			AP		0-0	22-11-51	D04069J	PERG	1F		GB01106	ST..	1A		ALL
2016B	24	Y2	AQ		2-9	22-11-51	D10135A	A06			TB1106Z	B013	1A		ALL
2016R	24	Y2	AQ		0-0	22-11-51	D10135A	B06			TB1106Z	A013	1A		ALL
2016Z			AQ		0-0	22-11-51	D10135A	DED			GB01106	ST..	1A		YC051-YC052, YL951-YR328
2016Z			AQ		0-0	22-11-51	GB01104	ST..	1A		GB01106	ST..	1A		YC053-YD158
2017B	24	Y2	AR		3-11	22-11-51	D43211J	B18			TB1106Z	B013	1A		ALL
2017R	24	Y2	AR		0-0	22-11-51	D43211J	A18			TB1106Z	A013	1A		ALL
2017Z			AR		0-0	22-11-51	D43211J	PERG	1F		GB01106	ST..	1A		ALL
2018B	24	Y2	AS		4-1	22-11-51	D41145J	B08			TB1106Z	B013	1A		ALL
2018R	24	Y2	AS		0-0	22-11-51	D41145J	B07			TB1106Z	A013	1A		ALL
2018Z			AS		0-0	22-11-51	D41145J	PERG	1F		GB01106	ST..	1A		ALL
2019B	24	Y2	AT		4-1	22-11-51	D41145J	B10			TB1106Z	B013	1A		ALL
2019R	24	Y2	AT		0-0	22-11-51	D41145J	B09			TB1106Z	A013	1A		ALL
2019Z			AT		0-0	22-11-51	D41145J	PERG	1F		GB01106	ST..	1A		ALL
2020B	24	Y2	AU		3-0	22-11-51	D45133J	B10			TB1110Z	B017	1A		YC051-YD157
2020B	24	Y2	AU		4-2	22-11-51	D45133J	B10			TB1110Z	B017	1A		YD158-YR328
2020R	24	Y2	AU		0-0	22-11-51	D45133J	A10			TB1110Z	A017	1A		ALL
2020Z			AU		0-0	22-11-51	D45133J	PERG	1F		GB01110	ST..	1A		ALL
2021B	24	Y2	AV		3-11	22-11-51	D10135A	J06			TB1110Z	B017	1A		YC051-YD157
2021B	24	Y2	AV		3-1	22-11-51	D10135A	J06			TB1110Z	B017	1A		YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0110

Page 25

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W0111	286A0111	E1-1 SHELF (continued)			
2021R	24 Y2 AV	0-0 22-11-51	D10135A K06	TB1110Z A017 1A	ALL
2021Z	24 Y2 AV	0-0 22-11-51	D10135A DED	GB01110 ST.. 1A	YC051-YC052, YL951-YR328
2021Z	24 Y2 AV	0-0 22-11-51	GB01104 ST.. 1A	GB01110 ST.. 1A	YC053-YD158
2022B	24 Y2 AX	3-0 22-11-51	D01153B B12	TB1110Z B017 1A	YC051-YD157
2022B	24 Y2 AX	4-1 22-11-51	D01153B B12	TB1110Z B017 1A	YD158-YR328
2022R	24 Y2 AX	0-0 22-11-51	D01153B A12	TB1110Z A017 1A	ALL
2022Z	24 Y2 AX	0-0 22-11-51	D01153B PERG 1A	GB01110 ST.. 1A	ALL
2023B	24 Y2 AY	3-1 22-11-51	D41145J B06	TB1110Z B017 1A	YC051-YD157
2023B	24 Y2 AY	4-3 22-11-51	D41145J B06	TB1110Z B017 1A	YD158-YR328
2023R	24 Y2 AY	0-0 22-11-51	D41145J B05	TB1110Z A017 1A	ALL
2023Z	24 Y2 AY	0-0 22-11-51	D41145J PERG 1F	GB01110 ST.. 1A	ALL
2024B	24 Y2 AZ	3-6 22-11-51	D04069J B07	TB1110Z B005 1A	YC051-YD157
2024B	24 Y2 AZ	4-8 22-11-51	D04069J B07	TB1110Z B005 1A	YD158-YR328
2024R	24 Y2 AZ	0-0 22-11-51	D04069J A07	TB1110Z A005 1A	ALL
2024Z	24 Y2 AZ	0-0 22-11-51	D04069J PERG 1F	GB01110 ST.. 1A	ALL
2025B	24 Y2 BA	2-10 22-11-51	D43211J B11	TB1110Z B005 1A	YC051-YD157
2025B	24 Y2 BA	4-0 22-11-51	D43211J B11	TB1110Z B005 1A	YD158-YR328
2025R	24 Y2 BA	0-0 22-11-51	D43211J A11	TB1110Z A005 1A	ALL
2025Z	24 Y2 BA	0-0 22-11-51	D43211J PERG 1F	GB01110 ST.. 1A	ALL
2026B	24 Y2 BB	2-10 22-11-51	D43211J B12	TB1110Z B005 1A	YC051-YD157
2026B	24 Y2 BB	4-0 22-11-51	D43211J B12	TB1110Z B005 1A	YD158-YR328
2026R	24 Y2 BB	0-0 22-11-51	D43211J A12	TB1110Z A005 1A	ALL
2026Z	24 Y2 BB	0-0 22-11-51	D43211J PERG 1F	GB01110 ST.. 1A	ALL
2027B	24 Y2 BC	1-6 22-11-51	D10009B B05	TB1110Z B005 1A	YC051-YD155
2027R	24 Y2 BC	0-0 22-11-51	D10009B A05	TB1110Z A005 1A	YC051-YD155
2027Z	24 Y2 BC	0-0 22-11-51	D10009B DED	GB01110 ST.. 1A	YC051-YD155
2028B	24 Y2 BD	2-10 22-11-51	D43211J B17	TB1110Z B005 1A	YC051-YD157
2028B	24 Y2 BD	4-0 22-11-51	D43211J B17	TB1110Z B005 1A	YD158-YR328
2028R	24 Y2 BD	0-0 22-11-51	D43211J A17	TB1110Z A005 1A	ALL
2028Z	24 Y2 BD	0-0 22-11-51	D43211J PERG 1F	GB01110 ST.. 1A	ALL
2029B	24 Y2 BE	2-10 22-11-51	D43211J B09	TB1110Z B005 1A	YC051-YD157
2029B	24 Y2 BE	4-0 22-11-51	D43211J B09	TB1110Z B005 1A	YD158-YR328
2029R	24 Y2 BE	0-0 22-11-51	D43211J A09	TB1110Z A005 1A	ALL
2029Z	24 Y2 BE	0-0 22-11-51	D43211J PERG 1F	GB01110 ST.. 1A	ALL
2030B	24 Y2 BF	4-0 22-11-51	D41121J B06	D10135A D10	ALL
2030R	24 Y2 BF	0-0 22-11-51	D41121J B05	D10135A E10	ALL
2030Z	24 Y2 BF	0-0 22-11-51	D41121J PERG 1F	GB01104 ST.. 1A	ALL
2031B	24 Y2 BG	4-0 22-11-51	D41121J B04	D10135A A10	ALL

WIRE LIST

D280A108

91-21-11

Section W0110

Page 26

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111				E1-1 SHELF (continued)										
2031R	24	Y2	BG		0-0	22-11-51	D41121J	B03			D10135A	B10			ALL
2031Z			BG		0-0	22-11-51	D41121J	PERG	1F		GB01104	ST..	1A		ALL
2032B	24	Y2	BH		4-7	22-11-51	D43317J	A17			D10135B	D10			ALL
2032R	24	Y2	BH		0-0	22-11-51	D43317J	A16			D10135B	E10			ALL
2032Z			BH		0-0	22-11-51	D43317J	PERG	1F		GB01104	ST..	1A		YC051-YD158
2032Z			BH		0-0	22-11-51	D43317J	PERG	1F		GB01105	ST..	1A		YL951-YR328
2033B	24	Y2	BI		4-7	22-11-51	D43317J	A14			D10135B	A10			ALL
2033R	24	Y2	BI		0-0	22-11-51	D43317J	A13			D10135B	B10			ALL
2033Z			BI		0-0	22-11-51	D43317J	PERG	1F		GB01104	ST..	1A		YC051-YD158
2033Z			BI		0-0	22-11-51	D43317J	PERG	1F		GB01105	ST..	1A		YL951-YR328
2034B	22	M2	BJ		4-7	22-12-31	D43317J	A19			D10135B	J11			YC051-YD155
2034R	22	M2	BJ		0-0	22-12-31	D43317J	A18			D10135B	K11			YC051-YD155
2034ZI			BJ		0-0	22-12-31	D43317J	A20			GB01104	ST..	1A		YC051-YD155
2034ZO			BJ		0-0	22-12-31	D43317J	PERG	1F		GB01104	ST..	1A		YC051-YD155
2035B	22	PB	BK		4-4	22-12-31	D04075J	B10			D10135B	E01			ALL
2035R	22	PB	BK		0-0	22-12-31	D04075J	B09			D10135B	E02			ALL
2036B	22	PB	BL		4-6	22-12-31	D04075J	B06			D10135A	E01			ALL
2036R	22	PB	BL		0-0	22-12-31	D04075J	B05			D10135A	E02			ALL
2037B	22	X2	BM		5-0	22-12-31	D10135A	C12			D04079J	A10			ALL
2037R	22	X2	BM		0-0	22-12-31	D10135A	D12			D04079J	A09			ALL
2037Z			BM		0-0	22-12-31	D10135A	DED			D04079J	PERG	1F		YC051-YC052
2037Z			BM		0-0	22-12-31	GB01104	ST..	1A		D04079J	PERG	1F		YC053-YR328
2038B	22	X2	BN		5-0	22-12-31	D10135A	A15			D04079J	A20			YC051-YD155
2038B	22	X2	BN		1-9	22-12-31	D10135A	A15			TB1104Y	B001	1A		YD157-YR328
2038R	22	X2	BN		0-0	22-12-31	D10135A	B15			D04079J	A19			YC051-YD155
2038R	22	X2	BN		0-0	22-12-31	D10135A	B15			TB1104Y	A001	1A		YD157-YR328
2038Z			BN		0-0	22-12-31	D10135A	DED			D04079J	PERG	1F		YC051-YC052
2038Z			BN		0-0	22-12-31	GB01104	ST..	1A		D04079J	PERG	1F		YC053-YD155
2038Z			BN		0-0	22-12-31	GB01104	ST..	1A		GB01104	ST..	1A		YD157-YD158
2038Z			BN		0-0	22-12-31	D10135A	DED			GB01104	ST..	1A		YL951-YR328
2039B	22	X2	BO		5-0	22-12-31	D10135A	A12			D04079J	B03			ALL
2039R	22	X2	BO		0-0	22-12-31	D10135A	A13			D04079J	B02			ALL
2039Z			BO		0-0	22-12-31	D10135A	DED			D04079J	PERG	1F		YC051-YC052
2039Z			BO		0-0	22-12-31	GB01104	ST..	1A		D04079J	PERG	1F		YC053-YR328
2040B	22	X2	BP		5-0	22-12-31	D10135A	D15			D04079J	A08			ALL
2040R	22	X2	BP		0-0	22-12-31	D10135A	E15			D04079J	A07			ALL
2040Z			BP		0-0	22-12-31	D10135A	DED			D04079J	PERG	1F		YC051-YC052, YL951-YR328
2040Z			BP		0-0	22-12-31	GB01104	ST..	1A		D04079J	PERG	1F		YC053-YD170

WIRE LIST

D280A108

91-21-11

Section W0110

Page 27

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111		286A0111			E1-1 SHELF (continued)											
2041B		22		M2	BQ	4-0	22-12-41	D10135A	J11			D41121J	B08			YC051-YD155
2041R		22		M2	BQ	0-0	22-12-41	D10135A	K11			D41121J	B07			YC051-YD155
2041ZI					BQ	0-0	22-12-41	D10135A	DED			D41121J	B09			YC051-YC070
2041ZI					BQ	0-0	22-12-41	GB01104	ST..	1A		D41121J	B09			YD151-YD155
2041ZO					BQ	0-0	22-12-41	D10135A	DED			D41121J	PERG	1F		YC051-YC052
2041ZO					BQ	0-0	22-12-41	GB01104	ST..	1A		D41121J	PERG	1F		YC053-YD155
2042B		22		X2	BR	2-3	22-18-11	D10135C	D04			TB1107Y	B013	1A		ALL
2042R		22		X2	BR	0-0	22-18-11	D10135C	E04			TB1107Y	A013	1A		ALL
2042Z					BR	0-0	22-18-11	D10135C	DED			TB1107Y	DED			YC051-YC068
2042Z					BR	0-0	22-18-11	GB01104	ST..	1A		GB01107	ST..	1A		YC070-YR328
2043B		22		X2	BS	4-5	22-18-11	D04425J	B05			TB1107Y	B013	1A		ALL
2043R		22		X2	BS	0-0	22-18-11	D04425J	B06			TB1107Y	A013	1A		ALL
2043Z					BS	0-0	22-18-11	D04425J	PERG	1F		TB1107Y	DED			YC051-YC068
2043Z					BS	0-0	22-18-11	D04425J	PERG	1F		GB01107	ST..	1A		YC070-YR328
2044B		22		X2	BT	3-6	22-18-11	D41121J	B11			TB1107Y	B013	1A		ALL
2044R		22		X2	BT	0-0	22-18-11	D41121J	B10			TB1107Y	A013	1A		ALL
2044Z					BT	0-0	22-18-11	D41121J	PERG	1F		TB1107Y	DED			YC051-YC068
2044Z					BT	0-0	22-18-11	D41121J	PERG	1F		GB01107	ST..	1A		YC070-YR328
2045B		24		Y2	ES	4-3	22-11-51	D41125J	A13			TB1110Z	B005	1A		YD158-YR328
2045R		24		Y2	ES	0-0	22-11-51	D41125J	A12			TB1110Z	A005	1A		YD158-YR328
2045Z					ES	0-0	22-11-51	D41125J	PERG	1F		GB01110	ST..	1A		YD158-YR328
2046B		24		Y2	GD	4-5	22-11-51	D41157J	B13			TB1110Z	B005	1A		YD158-YR328
2046R		24		Y2	GD	0-0	22-11-51	D41157J	B12			TB1110Z	A005	1A		YD158-YR328
2046Z					GD	0-0	22-11-51	D41157J	PERG	1F		GB01110	ST..	1A		YD158-YR328
2047B		22		X2	BW	3-5	22-18-11	D04425J	A03			D02209A	59			ALL
2047R		22		X2	BW	0-0	22-18-11	D04425J	A04			D02209A	58			ALL
2047Z					BW	0-0	22-18-11	D04425J	PERG	1F		D02209A	DED			ALL
2048B		22		PB	BX	4-8	22-18-11	D43317J	B18			D02209B	43			ALL
2048R		22		PB	BX	0-0	22-18-11	D43317J	B17			D02209B	42			ALL
2049B		22		PB	BY	2-9	22-18-11	D10135C	A01			D02209A	43			ALL
2049R		22		PB	BY	0-0	22-18-11	D10135C	B01			D02209A	42			ALL
2050B		24		Y2	BZ	1-9	31-62-11	D40019J	B20			SM00097		W		YC051-YD157
2050B		24		Y2	BZ	1-7	31-62-11	D40019J	B20			D04069J	B14			YD158-YR328
2050R		24		Y2	BZ	0-0	31-62-11	D40019J	B19			SM00095		W		YC051-YD157
2050R		24		Y2	BZ	0-0	31-62-11	D40019J	B19			D04069J	B13			YD158-YR328
2050Z					BZ	0-0	31-62-11	D40019J	PERG	1F		SM00099		W		YC051-YD157
2050Z					BZ	0-0	31-62-11	D40019J	PERG	1F		D04069J	PERG	1F		YD158-YR328
2051B		24		Y2	CA	2-8	27-32-12	D45113J	B13			TB1109Y	B005	1A		YC051-YD157
2051B		24		Y2	CA	4-0	27-32-12	D45113J	B13			TB1109Y	B005	1A		YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0110

Page 28

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To				Effectivity	
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W0111	286A0111			E1-1 SHELF (continued)												
2051R	24	Y2	CA	0-0	27-32-12	D45113J	A13				TB1109Y	A005	1A	ALL		
2051Z			CA	0-0	27-32-12	D45113J	PERG	1F			GB01109	ST..	1A	ALL		
2052B	24	Y2	CB	1-8	27-32-12	D10009A	D04				TB1109Y	B005	1A	YC051-YD155		
2052R	24	Y2	CB	0-0	27-32-12	D10009A	C04				TB1109Y	A005	1A	YC051-YD155		
2052Z			CB	0-0	27-32-12	D10009A	DED				GB01109	ST..	1A	YC051-YD155		
2053B	24	Y2	CC	2-10	27-32-12	D01153B	D12				TB1109Y	B005	1A	YC051-YD157		
2053B	24	Y2	CC	4-0	27-32-12	D01153B	D12				TB1109Y	B005	1A	YD158-YR328		
2053R	24	Y2	CC	0-0	27-32-12	D01153B	C12				TB1109Y	A005	1A	ALL		
2053Z			CC	0-0	27-32-12	D01153B	PERG	1A			GB01109	ST..	1A	ALL		
2054B	24	Y2	CD	3-9	27-32-12	D10135A	G04				TB1109Y	B005	1A	YC051-YD157		
2054B	24	Y2	CD	2-11	27-32-12	D10135A	G04				TB1109Y	B005	1A	YD158-YR328		
2054R	24	Y2	CD	0-0	27-32-12	D10135A	H04				TB1109Y	A005	1A	ALL		
2054Z			CD	0-0	27-32-12	D10135A	DED				GB01109	ST..	1A	ALL		
2055B	24	Y2	CE	3-11	34-33-11	D10009A	B03				TB1106Y	B011	1A	YC051-YD155		
2055B	24	Y2	CE	3-10	34-33-11	D41121J	B08				TB1106Y	B011	1A	YD157		
2055B	24	Y2	CE	3-11	34-33-11	D41121J	B08				TB1106Y	B011	1A	YD158-YR328		
2055R	24	Y2	CE	0-0	34-33-11	D10009A	A03				TB1106Y	A011	1A	YC051-YD155		
2055R	24	Y2	CE	0-0	34-33-11	D41121J	B07				TB1106Y	A011	1A	YD157-YR328		
2055Z			CE	0-0	34-33-11	D10009A	DED				GB01106	ST..	1A	YC051-YC052		
2055Z			CE	0-0	34-33-11	D10009A	PERG	1A			GB01106	ST..	1A	YC053-YD155		
2055Z			CE	0-0	34-33-11	D41121J	PERG	1F			GB01106	ST..	1A	YD157-YR328		
2056B	24	Y2	CF	2-9	34-33-11	D10135B	A04				TB1106Y	B011	1A	ALL		
2056R	24	Y2	CF	0-0	34-33-11	D10135B	B04				TB1106Y	A011	1A	ALL		
2056Z			CF	0-0	34-33-11	D10135B	DED				GB01106	ST..	1A	ALL		
2057B	24	Y2	CG	4-2	34-33-11	D41145J	A08				TB1106Y	B011	1A	ALL		
2057R	24	Y2	CG	0-0	34-33-11	D41145J	A07				TB1106Y	A011	1A	ALL		
2057Z			CG	0-0	34-33-11	D41145J	PERG	1F			GB01106	ST..	1A	ALL		
2058B	24	Y2	CH	3-9	34-45-11	D02743E	H07				D41157J	B08		ALL		
2058R	24	Y2	CH	0-0	34-45-11	D02743E	G07				D41157J	B07		ALL		
2058Z			CH	0-0	34-45-11	GB01103	ST..	1A			D41157J	PERG	1F	ALL		
2059B	24	Y2	CI	3-8	22-11-51	D04069J	B09				TB1110Z	B017	1A	YC051-YD157		
2059B	24	Y2	CI	4-10	22-11-51	D04069J	B09				TB1110Z	B017	1A	YD158-YR328		
2059R	24	Y2	CI	0-0	22-11-51	D04069J	A09				TB1110Z	A017	1A	ALL		
2059Z			CI	0-0	22-11-51	D04069J	PERG	1F			GB01110	ST..	1A	ALL		
2060B	22	X2	CJ	4-0	22-11-31	D41121J	B02				D10135A	F11		YC051-YD155		
2060B	24	Y2	CJ	4-7	22-11-51	D43317J	A11				D10135B	F11		YD157-YR328		
2060R	22	X2	CJ	0-0	22-11-31	D41121J	B01				D10135A	G11		YC051-YD155		
2060R	24	Y2	CJ	0-0	22-11-51	D43317J	A10				D10135B	G11		YD157-YR328		
2060Z			CJ	0-0	22-11-31	D41121J	PERG	1F			GB01104	ST..	1A	YC051-YD155		

WIRE LIST

D280A108

91-21-11

Section W0110

Page 29

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111		286A0111					E1-1 SHELF (continued)									
2060Z					CJ	0-0	22-11-51	D43317J	PERG	1F		GB01104	ST..	1A		YD157-YD158
2060Z					CJ	0-0	22-11-51	D43317J	PERG	1F		GB01105	ST..	1A		YL951-YR328
2061B		24	Y2		CK	1-6	27-32-22	D10009B		D04		TB1110Y	B001	1A		YC051-YD155
2061R		24	Y2		CK	0-0	27-32-22	D10009B		C04		TB1110Y	A001	1A		YC051-YD155
2061Z					CK	0-0	27-32-22	D10009B		DED		GB01110	ST..	1A		YC051-YD155
2062B		24	Y2		CL	2-11	27-32-22	D01153A		D09		TB1110Y	B001	1A		YC051-YD155
2062B		24	Y2		CL	6-7	27-32-22	D01153A		D09		D41163J	B04			YD157
2062B		24	Y2		CL	6-6	27-32-22	D01153A		D09		D41163J	B04			YD158-YR328
2062R		24	Y2		CL	0-0	27-32-22	D01153A		C09		TB1110Y	A001	1A		YC051-YD155
2062R		24	Y2		CL	0-0	27-32-22	D01153A		C09		D41163J	A04			YD157-YR328
2062Z					CL	0-0	27-32-22	D01153A		PERG	1A	GB01110	ST..	1A		YC051-YD155
2062Z					CL	0-0	27-32-22	D01153A		PERG	1A	D41163J	PERG	1F		YD157-YR328
2063B		24	Y2		CM	6-0	27-32-22	D41163J		B04		TB1110Y	B001	1A		YC051-YD155
2063R		24	Y2		CM	0-0	27-32-22	D41163J		A04		TB1110Y	A001	1A		YC051-YD155
2063Z					CM	0-0	27-32-22	D41163J		PERG	1F	GB01110	ST..	1A		YC051-YD155
2064B		24	Y2		CN	3-8	34-33-11	D01153B		B13		TB1108Y	B003	1A		YC051-YD157
2064B		24	Y2		CN	3-7	34-33-11	D01153B		B13		TB1108Y	B003	1A		YD158-YR328
2064R		24	Y2		CN	0-0	34-33-11	D01153B		A13		TB1108Y	A003	1A		ALL
2064Z					CN	0-0	34-33-11	D01153B		PERG	1A	GB01108	ST..	1A		ALL
2065B		24	Y2		CO	3-3	34-33-11	D02743E		J13		TB1108Y	B003	1A		ALL
2065R		24	Y2		CO	0-0	34-33-11	D02743E		H13		TB1108Y	A003	1A		ALL
2065Z					CO	0-0	34-33-11	D02743E		DED		GB01108	ST..	1A		ALL
2066B		24	Y2		CP	3-9	34-33-11	D41145J		A10		TB1108Y	B003	1A		ALL
2066R		24	Y2		CP	0-0	34-33-11	D41145J		A09		TB1108Y	A003	1A		ALL
2066Z					CP	0-0	34-33-11	D41145J		PERG	1F	GB01108	ST..	1A		ALL
2067B		24	Y2		CQ	4-3	34-45-11	D43211J		B02		TB1106Y	B001	1A		ALL
2067R		24	Y2		CQ	0-0	34-45-11	D43211J		A02		TB1106Y	A001	1A		ALL
2067Z					CQ	0-0	34-45-11	D43211J		PERG	1F	GB01106	ST..	1A		ALL
2068B		24	Y2		CR	4-2	34-45-11	D45113J		B12		TB1106Y	B001	1A		ALL
2068R		24	Y2		CR	0-0	34-45-11	D45113J		A12		TB1106Y	A001	1A		ALL
2068Z					CR	0-0	34-45-11	D45113J		PERG	1F	GB01106	ST..	1A		ALL
2069B		24	Y2		CS	2-7	34-45-11	D02743E		D07		TB1106Y	B001	1A		ALL
2069R		24	Y2		CS	0-0	34-45-11	D02743E		C07		TB1106Y	A001	1A		ALL
2069Z					CS	0-0	34-45-11	D02743E		DED		GB01106	ST..	1A		ALL
2070B		24	Y2		CT	5-0	34-45-21	D02743E		K15		D41125J	A06			YC051-YD157
2070B		24	Y2		CT	5-1	34-45-21	D02743E		K15		D41125J	A06			YD158-YR328
2070R		24	Y2		CT	0-0	34-45-21	D02743E		J15		D41125J	A05			ALL
2070Z					CT	0-0	34-45-21	GB01103		ST..	1A	D41125J	PERG	1F		ALL
2071B		24	Y2		CU	5-0	34-45-21	D02743E		G14		D41125J	B06			YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0110

Page 30

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111				E1-1 SHELF (continued)										
2071B	24		Y2	CU	5-1	34-45-21	D02743E	G14			D41125J	B06			YD158-YR328
2071R	24		Y2	CU	0-0	34-45-21	D02743E	F14			D41125J	B05			ALL
2071Z				CU	0-0	34-45-21	GB01103	ST..	1A		D41125J	PERG	1F		ALL
2072B	24		Y2	CV	3-9	34-45-21	D02743E	B14			D41157J	A13			ALL
2072R	24		Y2	CV	0-0	34-45-21	D02743E	A14			D41157J	A12			ALL
2072Z				CV	0-0	34-45-21	GB01103	ST..	1A		D41157J	PERG	1F		ALL
2073B	24		Y2	CX	3-9	34-45-21	D02743E	J14			D41157J	A15			ALL
2073R	24		Y2	CX	0-0	34-45-21	D02743E	H14			D41157J	A14			ALL
2073Z				CX	0-0	34-45-21	GB01103	ST..	1A		D41157J	PERG	1F		ALL
2074B	24		M5	CY	2-7	34-49-11	D41155J	A19			D01153B	D13			YC051-YD157
2074B	24		M5	CY	2-8	34-49-11	D41155J	A19			D01153B	D13			YD158-YR328
2074R	24		M5	CY	0-0	34-49-11	D41155J	A18			D01153B	C13			ALL
2074ZI				CY	0-0	34-49-11	D41155J	A20			D01153B	PERG	1A		ALL
2074ZO				CY	0-0	34-49-11	D41155J	PERG	1F		D01153B	PERG	1A		ALL
2075B	24		Y2	CZ	4-3	34-49-11	D41157J	B15			TB1108Y	B001	1A		ALL
2075R	24		Y2	CZ	0-0	34-49-11	D41157J	B14			TB1108Y	A001	1A		ALL
2075Z				CZ	0-0	34-49-11	D41157J	PERG	1F		GB01108	ST..	1A		ALL
2076B	24		Y2	DA	3-7	34-49-11	D43211J	B03			TB1108Y	B001	1A		YC051-YD157
2076B	24		Y2	DA	3-8	34-49-11	D43211J	B03			TB1108Y	B001	1A		YD158-YR328
2076R	24		Y2	DA	0-0	34-49-11	D43211J	A03			TB1108Y	A001	1A		ALL
2076Z				DA	0-0	34-49-11	D43211J	PERG	1F		GB01108	ST..	1A		ALL
2077B	24		Y2	DB	3-8	34-49-11	D01153B	D01			TB1108Y	B001	1A		YC051-YD157
2077B	24		Y2	DB	3-7	34-49-11	D01153B	D01			TB1108Y	B001	1A		YD158-YR328
2077R	24		Y2	DB	0-0	34-49-11	D01153B	C01			TB1108Y	A001	1A		ALL
2077Z				DB	0-0	34-49-11	D01153B	PERG	1A		GB01108	ST..	1A		ALL
2078B	24		Y2	DC	4-4	34-55-11	D10135B	G04			D41125J	A02			ALL
2078R	24		Y2	DC	0-0	34-55-11	D10135B	H04			D41125J	A01			ALL
2078Z				DC	0-0	34-55-11	GB01104	ST..	1A		D41125J	PERG	1F		ALL
2079B	24		Y2	DD	3-7	22-31-31	D41159J	B01			TB1109Y	B007	1A		YC051-YD157
2079B	24		Y2	DD	4-10	22-31-31	D41159J	B01			TB1109Y	B007	1A		YD158-YR328
2079R	24		Y2	DD	0-0	22-31-31	D41159J	A01			TB1109Y	A007	1A		ALL
2079Z				DD	0-0	22-31-31	D41159J	PERG	1F		GB01109	ST..	1A		ALL
2080B	24		Y2	DE	1-6	22-31-31	D10009B	D10			TB1109Y	B007	1A		YC051-YD155
2080B	24		Y2	DE	3-7	22-31-31	D10135B	J02			TB1109Y	B007	1A		YD157
2080B	24		Y2	DE	2-10	22-31-31	D10135B	J02			TB1109Y	B007	1A		YD158-YR328
2080R	24		Y2	DE	0-0	22-31-31	D10009B	C10			TB1109Y	A007	1A		YC051-YD155
2080R	24		Y2	DE	0-0	22-31-31	D10135B	H03			TB1109Y	A007	1A		YD157-YR328
2080Z				DE	0-0	22-31-31	D10009B	DED			GB01109	ST..	1A		YC051-YD155
2080Z				DE	0-0	22-31-31	D10135B	DED			GB01109	ST..	1A		YD157-YR328

WIRE LIST

D280A108

91-21-11

Section W0110

Page 31

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111			E1-1 SHELF (continued)											
2081B	24	Y2	DF		6-3	22-31-41	D41161J	B01			TB1109Y	B007	1A		YC051-YD157
2081B	24	Y2	DF		4-11	22-31-41	D41161J	B01			TB1109Y	B007	1A		YD158-YR328
2081R	24	Y2	DF		0-0	22-31-41	D41161J	A01			TB1109Y	A007	1A		ALL
2081Z			DF		0-0	22-31-41	D41161J	PERG	1F		GB01109	ST..	1A		ALL
2082B	24	PL	DG		3-10	22-31-31	D41159J	B02			D10009A	C15			YC051-YD155
2082B	24	PL	DG		4-11	22-31-31	D41159J	B02			D10135A	B14			YD157-YR328
2082R	24	PL	DG		0-0	22-31-31	D41159J	A02			D10009A	D15			YC051-YD155
2082R	24	PL	DG		0-0	22-31-31	D41159J	A02			D10135A	A14			YD157-YR328
2083B	22	PB	DH		3-10	22-31-31	D41159J	B03			D10009A	C13			YC051-YD155
2083B	22	PB	DH		4-11	22-31-31	D41159J	B03			D10135A	B09			YD157-YR328
2083R	22	PB	DH		0-0	22-31-31	D41159J	A03			D10009A	D13			YC051-YD155
2083R	22	PB	DH		0-0	22-31-31	D41159J	A03			D10135A	A09			YD157-YR328
2084B	24	Y2	DI		3-10	22-31-31	D41159J	B04			D10009A	D06			YC051-YD155
2084B	24	Y2	DI		4-11	22-31-31	D41159J	B04			D10135A	D05			YD157-YR328
2084R	24	Y2	DI		0-0	22-31-31	D41159J	A04			D10009A	C06			YC051-YD155
2084R	24	Y2	DI		0-0	22-31-31	D41159J	A04			D10135A	C06			YD157-YR328
2084Z			DI		0-0	22-31-31	D41159J	PERG	1F		GB01109	ST..	1A		YC051-YD170, YN231
2084Z			DI		0-0	22-31-31	D41159J	PERG	1F		GB01105	ST..	1A		YL951-YL999, YN232-YR328
2085B	24	Y2	DJ		6-6	22-31-41	D41161J	B02			D10009B	C15			YC051-YD155
2085B	24	Y2	DJ		4-11	22-31-41	D41161J	B02			D10135B	B14			YD157-YR328
2085R	24	Y2	DJ		0-0	22-31-41	D41161J	A02			D10009B	D15			YC051-YD155
2085R	24	Y2	DJ		0-0	22-31-41	D41161J	A02			D10135B	A14			YD157-YR328
2085Z			DJ		0-0	22-31-41	D41161J	PERG	1F		GB01109	ST..	1A		YC051-YD170, YN231
2085Z			DJ		0-0	22-31-41	D41161J	PERG	1F		GB01105	ST..	1A		YL951-YL999, YN232-YR328
2086B	22	X2	DK		6-6	22-31-41	D41161J	B03			D10009B	C13			YC051-YD155
2086B	22	X2	DK		4-11	22-31-41	D41161J	B03			D10135B	B09			YD157-YR328
2086R	22	X2	DK		0-0	22-31-41	D41161J	A03			D10009B	D13			YC051-YD155
2086R	22	X2	DK		0-0	22-31-41	D41161J	A03			D10135B	A09			YD157-YR328
2086Z			DK		0-0	22-31-41	D41161J	PERG	1F		GB01109	ST..	1A		YC051-YD170, YN231
2086Z			DK		0-0	22-31-41	D41161J	PERG	1F		GB01105	ST..	1A		YL951-YL999, YN232-YR328
2087B	24	Y2	DL		6-6	22-31-41	D41161J	B04			D10009B	D06			YC051-YD155
2087B	24	Y2	DL		4-11	22-31-41	D41161J	B04			D10135B	D05			YD157-YR328
2087R	24	Y2	DL		0-0	22-31-41	D41161J	A04			D10009B	C06			YC051-YD155
2087R	24	Y2	DL		0-0	22-31-41	D41161J	A04			D10135B	C06			YD157-YR328
2087Z			DL		0-0	22-31-41	D41161J	PERG	1F		GB01109	ST..	1A		YC051-YD170, YN231

WIRE LIST

D280A108

91-21-11

Section W0110

Page 32

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From				To						
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111			E1-1 SHELF (continued)											
2087Z				DL	0-0	22-31-41	D41161J	PERG	1F		GB01105	ST..	1A		YL951-YL999, YN232-YR328
2088B	24	Y2	DM		3-10	22-31-52	D41155J	A10			TB1104Z	B005	1A		ALL
2088R	24	Y2	DM		0-0	22-31-52	D41155J	A09			TB1104Z	A005	1A		ALL
2088Z			DM		0-0	22-31-52	D41155J	PERG	1F		GB01104	ST..	1A		ALL
2089B	24	Y2	DN		3-9	22-31-52	D10009A	D10			TB1104Z	B005	1A		YC051-YD155
2089B	24	Y2	DN		1-8	22-31-52	D10135B	F08			TB1104Z	B005	1A		YD157-YR328
2089R	24	Y2	DN		0-0	22-31-52	D10009A	C10			TB1104Z	A005	1A		YC051-YD155
2089R	24	Y2	DN		0-0	22-31-52	D10135B	F09			TB1104Z	A005	1A		YD157-YR328
2089Z			DN		0-0	22-31-52	D10009A	DED			GB01104	ST..	1A		YC051-YD155
2089Z			DN		0-0	22-31-52	D10135B	DED			GB01104	ST..	1A		YD157-YR328
2090B	24	Y2	DO		1-9	22-31-52	D10135A	A04			TB1104Z	B005	1A		ALL
2090R	24	Y2	DO		0-0	22-31-52	D10135A	B04			TB1104Z	A005	1A		ALL
2090Z			DO		0-0	22-31-52	D10135A	DED			GB01104	ST..	1A		ALL
2091B	24	Y2	DP		4-3	22-31-52	D41157J	A08			TB1104Z	B005	1A		ALL
2091R	24	Y2	DP		0-0	22-31-52	D41157J	A07			TB1104Z	A005	1A		ALL
2091Z			DP		0-0	22-31-52	D41157J	PERG	1F		GB01104	ST..	1A		ALL
2092B	24	Y2	DQ		4-3	22-31-52	D41157J	A10			TB1104Z	B005	1A		ALL
2092R	24	Y2	DQ		0-0	22-31-52	D41157J	A09			TB1104Z	A005	1A		ALL
2092Z			DQ		0-0	22-31-52	D41157J	PERG	1F		GB01104	ST..	1A		ALL
2093B	24	Y2	DR		3-11	22-31-52	D43211J	B01			TB1104Z	B005	1A		ALL
2093R	24	Y2	DR		0-0	22-31-52	D43211J	A01			TB1104Z	A005	1A		ALL
2093Z			DR		0-0	22-31-52	D43211J	PERG	1F		GB01104	ST..	1A		ALL
2094B	24	Y2	DS		4-6	22-31-52	D41163J	B10			TB1104Z	B005	1A		ALL
2094R	24	Y2	DS		0-0	22-31-52	D41163J	A10			TB1104Z	A005	1A		ALL
2094Z			DS		0-0	22-31-52	D41163J	PERG	1F		GB01104	ST..	1A		ALL
2095B	24	Y2	DT		2-10	34-21-13	D01153B	B06			TB1110Z	B009	1A		YC051-YD157
2095B	24	Y2	DT		3-11	34-21-13	D01153B	B06			TB1110Z	B009	1A		YD158-YR328
2095R	24	Y2	DT		0-0	34-21-13	D01153B	A06			TB1110Z	A009	1A		ALL
2095Z			DT		0-0	34-21-13	D01153B	PERG	1A		GB01110	ST..	1A		ALL
2096B	24	Y2	DU		1-8	34-21-13	D10009A	D08			TB1110Z	B009	1A		YC051-YD155
2096R	24	Y2	DU		0-0	34-21-13	D10009A	C08			TB1110Z	A009	1A		YC051-YD155
2096Z			DU		0-0	34-21-13	D10009A	DED			GB01110	ST..	1A		YC051-YD155
2097B	24	Y2	DV		2-6	34-21-13	D00235B	89			TB1110Z	B009	1A		YC051-YD157
2097B	24	Y2	DV		3-1	34-21-13	D00235B	89			TB1110Z	B009	1A		YD158-YR328
2097R	24	Y2	DV		0-0	34-21-13	D00235B	46			TB1110Z	A009	1A		ALL
2097Z			DV		0-0	34-21-13	D00235B			EI	GB01110	ST..	1A		ALL
2098B	24	Y2	DW		4-4	34-21-13	D02743E	B07			TB1110Z	B009	1A		YC051-YD157
2098B	24	Y2	DW		3-6	34-21-13	D02743E	B07			TB1110Z	B009	1A		YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0110

Page 33

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111		286A0111			E1-1 SHELF (continued)											
2098R		24		Y2	DW	0-0	34-21-13	D02743E	A07			TB1110Z	A009	1A		ALL
2098Z					DW	0-0	34-21-13	D02743E	DED			GB01110	ST..	1A		ALL
2099B		24		Y2	DX	2-8	34-21-13	D41121J	B13			TB1110Z	B009	1A		YC051-YD157
2099B		24		Y2	DX	3-10	34-21-13	D41121J	B13			TB1110Z	B009	1A		YD158-YR328
2099R		24		Y2	DX	0-0	34-21-13	D41121J	B12			TB1110Z	A009	1A		ALL
2099Z					DX	0-0	34-21-13	D41121J	PERG	1F		GB01110	ST..	1A		ALL
2101B		24		Y2	DY	3-2	34-21-13	D41125J	B09			TB1110Z	B009	1A		YC051-YD157
2101B		24		Y2	DY	4-4	34-21-13	D41125J	B09			TB1110Z	B009	1A		YD158-YR328
2101R		24		Y2	DY	0-0	34-21-13	D41125J	A09			TB1110Z	A009	1A		ALL
2101Z					DY	0-0	34-21-13	D41125J	PERG	1F		GB01110	ST..	1A		ALL
2102B		24		Y2	DZ	2-9	34-21-13	D41155J	A13			TB1110Z	B009	1A		YC051-YD157
2102B		24		Y2	DZ	4-0	34-21-13	D41155J	A13			TB1110Z	B009	1A		YD158-YR328
2102R		24		Y2	DZ	0-0	34-21-13	D41155J	A12			TB1110Z	A009	1A		ALL
2102Z					DZ	0-0	34-21-13	D41155J	PERG	1F		GB01110	ST..	1A		ALL
2103B		24		Y2	EA	4-0	34-21-13	D41155J	A15			D10135B	K02			ALL
2103R		24		Y2	EA	0-0	34-21-13	D41155J	A14			D10135B	K03			ALL
2103Z					EA	0-0	34-21-13	D41155J	PERG	1F		GB01104	ST..	1A		ALL
2104B		24		Y2	EB	3-1	34-21-14	D01153B	B11			TB1110Y	B021	1A		YC051-YD157
2104B		24		Y2	EB	4-2	34-21-14	D01153B	B11			TB1110Y	B021	1A		YD158-YR328
2104R		24		Y2	EB	0-0	34-21-14	D01153B	A11			TB1110Y	A021	1A		ALL
2104Z					EB	0-0	34-21-14	D01153B	PERG	1A		GB01110	ST..	1A		ALL
2105B		24		Y2	EC	2-11	34-21-14	D00728B	A05			TB1110Y	B021	1A		ALL
2105R		24		Y2	EC	0-0	34-21-14	D00728B	A04			TB1110Y	A021	1A		ALL
2105Z					EC	0-0	34-21-14	D00728B	PERG	1A		GB01110	ST..	1A		ALL
2106B		24		Y2	ED	6-2	34-21-14	D43317J	B02			TB1110Y	B021	1A		YC051-YD157
2106B		24		Y2	ED	4-11	34-21-14	D43317J	B02			TB1110Y	B021	1A		YD158-YR328
2106R		24		Y2	ED	0-0	34-21-14	D43317J	B01			TB1110Y	A021	1A		ALL
2106Z					ED	0-0	34-21-14	D43317J	PERG	1F		GB01110	ST..	1A		ALL
2107B		24		Y2	EF	3-0	34-21-14	D41155J	A02			TB1110Y	B021	1A		YC051-YD157
2107B		24		Y2	EF	4-2	34-21-14	D41155J	A02			TB1110Y	B021	1A		YD158-YR328
2107R		24		Y2	EF	0-0	34-21-14	D41155J	A01			TB1110Y	A021	1A		ALL
2107Z					EF	0-0	34-21-14	D41155J	PERG	1F		GB01110	ST..	1A		ALL
2108B		24		Y2	EG	4-0	34-21-14	D10135B	D04			D41155J	A04			ALL
2108R		24		Y2	EG	0-0	34-21-14	D10135B	E04			D41155J	A03			ALL
2108Z					EG	0-0	34-21-14	GB01104	ST..	1A		D41155J	PERG	1F		ALL
2109B		24		Y2	EH	3-0	34-21-14	D10009A	D02			D41155J	A06			YC051-YD155
2109R		24		Y2	EH	0-0	34-21-14	D10009A	C02			D41155J	A05			YC051-YD155
2109Z					EH	0-0	34-21-14	GB01110	ST..	1A		D41155J	PERG	1F		YC051-YD155
2110B		22		X2	EI	2-11	34-21-15	D43211J	B04			D00235B	99			ALL

WIRE LIST

D280A108

91-21-11

Section W0110

Page 34

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description		From				To					
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W0111		286A0111			E1-1 SHELF (continued)											
2110R	22	X2	EI		0-0	34-21-15	D43211J	A04			D00235B	121			ALL	
2110Z			EI		0-0	34-21-15	D43211J	PERG	1F		D00235B			EI	ALL	
2111B	24	Y2	EJ		3-9	34-21-23	D10135A	K02			TB1109Z	B009	1A		YC051-YD157	
2111B	24	Y2	EJ		3-0	34-21-23	D10135A	K02			TB1109Z	B009	1A		YD158-YR328	
2111R	24	Y2	EJ		0-0	34-21-23	D10135A	K03			TB1109Z	A009	1A		ALL	
2111Z			EJ		0-0	34-21-23	D10135A	DED			GB01109	ST..	1A		ALL	
2112B	24	Y2	EK		1-7	34-21-23	D10009B	D08			TB1109Z	B009	1A		YC051-YD155	
2112R	24	Y2	EK		0-0	34-21-23	D10009B	C08			TB1109Z	A009	1A		YC051-YD155	
2112Z			EK		0-0	34-21-23	D10009B	DED			GB01109	ST..	1A		YC051-YD155	
2113B	24	Y2	EL		2-6	34-21-23	D00235B	119			TB1109Z	B009	1A		YC051-YD157	
2113B	24	Y2	EL		3-2	34-21-23	D00235B	119			TB1109Z	B009	1A		YD158-YR328	
2113R	24	Y2	EL		0-0	34-21-23	D00235B	120			TB1109Z	A009	1A		ALL	
2113Z			EL		0-0	34-21-23	D00235B			EI	GB01109	ST..	1A		ALL	
2114B	24	Y2	EM		3-2	34-21-23	D41125J	B08			TB1109Z	B009	1A		YC051-YD157	
2114B	24	Y2	EM		4-6	34-21-23	D41125J	B08			TB1109Z	B009	1A		YD158-YR328	
2114R	24	Y2	EM		0-0	34-21-23	D41125J	A08			TB1109Z	A009	1A		ALL	
2114Z			EM		0-0	34-21-23	D41125J	PERG	1F		GB01109	ST..	1A		ALL	
2115B	24	Y2	EN		5-4	34-21-23	D41157J	B03			TB1109Z	B009	1A		YC051-YD157	
2115B	24	Y2	EN		4-5	34-21-23	D41157J	B03			TB1109Z	B009	1A		YD158-YR328	
2115R	24	Y2	EN		0-0	34-21-23	D41157J	B02			TB1109Z	A009	1A		ALL	
2115Z			EN		0-0	34-21-23	D41157J	PERG	1F		GB01109	ST..	1A		ALL	
2116B	24	Y2	EO		5-5	34-21-24	D10009B	D02			D41157J	A04			YC051-YD155	
2116B	24	Y2	EO		4-6	34-21-24	D10135A	J04			D41157J	A04			YD157-YR328	
2116R	24	Y2	EO		0-0	34-21-24	D10009B	C02			D41157J	A03			YC051-YD155	
2116R	24	Y2	EO		0-0	34-21-24	D10135A	K04			D41157J	A03			YD157-YR328	
2116Z			EO		0-0	34-21-24	GB01109	ST..	1A		D41157J	PERG	1F		YC051-YD170, YN231	
2116Z			EO		0-0	34-21-24	GB01105	ST..	1A		D41157J	PERG	1F		YL951-YL999, YN232-YR328	
2117B	24	Y2	EP		1-11	34-61-14	D10009A	B05			TB1110Y	B023	1A		YC051-YD155	
2117R	24	Y2	EP		0-0	34-61-14	D10009A	A05			TB1110Y	A023	1A		YC051-YD155	
2117Z			EP		0-0	34-61-14	D10009A	DED			GB01110	ST..	1A		YC051-YD155	
2118B	24	Y2	EQ		4-0	34-61-14	D10135A	D04			TB1110Y	B023	1A		YC051-YD155	
2118B	24	Y2	EQ		4-1	34-61-14	D10135A	D04			D41155J	B03			YD157-YR328	
2118R	24	Y2	EQ		0-0	34-61-14	D10135A	E04			TB1110Y	A023	1A		YC051-YD155	
2118R	24	Y2	EQ		0-0	34-61-14	D10135A	E04			D41155J	B02			YD157-YR328	
2118Z			EQ		0-0	34-61-14	D10135A	DED			GB01110	ST..	1A		YC051-YD155	
2118Z			EQ		0-0	34-61-14	D10135A	DED			D41155J	PERG	1F		YD157-YR328	
2119B	24	Y2	ER		3-0	34-61-14	D41155J	B03			TB1110Y	B023	1A		YC051-YD155	
2119R	24	Y2	ER		0-0	34-61-14	D41155J	B02			TB1110Y	A023	1A		YC051-YD155	

WIRE LIST

D280A108

91-21-11

Section W0110

Page 35

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111		286A0111			E1-1 SHELF (continued)											
2119Z					ER	0-0	34-61-14	D41155J	PERG	1F		GB01110	ST..	1A		YC051-YD155
2121B		22	X2		ET	2-7	34-61-15	D01153B	D10			D41155J	B19			YC051-YD157
2121B		22	X2		ET	2-8	34-61-15	D01153B	D10			D41155J	B19			YD158-YR328
2121R		22	X2		ET	0-0	34-61-15	D01153B	C10			D41155J	B18			ALL
2121Z					ET	0-0	34-61-15	D01153B	PERG	1A		D41155J	PERG	1F		ALL
2122B		24	Y2		EU	3-11	34-31-11	D45113J	B05			D10135B	G02			ALL
2122R		24	Y2		EU	0-0	34-31-11	D45113J	A05			D10135B	H02			ALL
2122Z					EU	0-0	34-31-11	D45113J	PERG	1F		GB01104	ST..	1A		ALL
2123B		24	Y2		EV	2-6	34-31-11	D45113J	B06			D01153B	D11			YC051-YD157
2123B		24	Y2		EV	2-8	34-31-11	D45113J	B06			D01153B	D11			YD158-YR328
2123R		24	Y2		EV	0-0	34-31-11	D45113J	A06			D01153B	C11			ALL
2123Z					EV	0-0	34-31-11	D45113J	PERG	1F		D01153B	PERG	1A		ALL
2124B		24	Y2		EW	4-9	34-31-21	D43317J	B20			D10135A	G02			ALL
2124R		24	Y2		EW	0-0	34-31-21	D43317J	B19			D10135A	H02			ALL
2124Z					EW	0-0	34-31-21	D43317J	PERG	1F		GB01104	ST..	1A		ALL
2125B		24	Y2		EX	6-6	34-31-21	D43317J	B06			D01153A	D08			YC051-YC052
2125B		24	Y2		EX	6-6	34-31-21	D43317J	B06			D01153A	D05			YC065-YD157
2125B		24	Y2		EX	6-5	34-31-21	D43317J	B06			D01153A	D05			YD158-YR328
2125R		24	Y2		EX	0-0	34-31-21	D43317J	B05			D01153A	C08			YC051-YC052
2125R		24	Y2		EX	0-0	34-31-21	D43317J	B05			D01153A	C05			YC065-YR328
2125Z					EX	0-0	34-31-21	D43317J	PERG	1F		D01153A	PERG	1A		YC051-YC052, YC065-YR328
2126B		24	Y2		EY	3-11	34-51-11	D10135B	G08			D45113J	B07			ALL
2126R		24	Y2		EY	0-0	34-51-11	D10135B	H08			D45113J	A07			ALL
2126Z					EY	0-0	34-51-11	GB01104	ST..	1A		D45113J	PERG	1F		ALL
2127B		24	Y2		EZ	3-2	31-62-12	D45113J	B09			D40019J	A20			ALL
2127R		24	Y2		EZ	0-0	31-62-12	D45113J	A09			D40019J	A19			ALL
2127Z					EZ	0-0	31-62-12	D45113J	PERG	1F		D40019J	PERG	1F		ALL
2128B		24	Y2		HA	3-11	31-62-15	D45113J	B10			D10135B	A02			ALL
2128R		24	Y2		HA	0-0	31-62-15	D45113J	A10			D10135B	B02			ALL
2128Z					HA	0-0	31-62-15	D45113J	PERG	1F		GB01104	ST..	1A		ALL
2129B		24	Y2		HB	2-6	31-62-15	D45113J	B11			D01153B	B10			YC051-YD157
2129B		24	Y2		HB	2-8	31-62-15	D45113J	B11			D01153B	B10			YD158-YR328
2129R		24	Y2		HB	0-0	31-62-15	D45113J	A11			D01153B	A10			ALL
2129Z					HB	0-0	31-62-15	D45113J	PERG	1F		D01153B	PERG	1A		ALL
2130B		24	Y2		HC	4-7	31-62-25	D41147J	A02			D10135A	A02			ALL
2130R		24	Y2		HC	0-0	31-62-25	D41147J	A01			D10135A	B02			ALL
2130Z					HC	0-0	31-62-25	D41147J	PERG	1F		GB01104	ST..	1A		ALL
2131B		24	Y2		HD	6-5	31-62-25	D41147J	A06			D01153A	B09			YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0110

Page 36

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description		From				To					
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111		286A0111			E1-1 SHELF (continued)											
2131B		24		Y2	HD	6-4	31-62-25	D41147J	A06			D01153A	B09			YD158-YR328
2131R		24		Y2	HD	0-0	31-62-25	D41147J	A05			D01153A	A09			ALL
2131Z					HD	0-0	31-62-25	D41147J	PERG	1F		D01153A	PERG	1A		ALL
2132B		22		PB	HE	2-11	24-28-41	D40454J	B02			D41125J	A20			ALL
2132R		22		PB	HE	0-0	24-28-41	D40454J	B01			D41125J	A19			ALL
2133B		24		Y2	HF	3-2	73-24-11	D40452J	B05			D10009A	B01			YC051-YD155
2133B		24		Y2	HF	4-3	73-24-11	D40452J	B05			D10135A	C04			YD157-YR328
2133R		24		Y2	HF	0-0	73-24-11	D40452J	B06			D10009A	A01			YC051-YD155
2133R		24		Y2	HF	0-0	73-24-11	D40452J	B06			D10135A	B05			YD157-YR328
2133Z					HF	0-0	73-24-11	D40452J	PERG	1F		GB01110	ST..	1A		YC051-YD170, YN231
2133Z					HF	0-0	73-24-11	D40452J	PERG	1F		GB01105	ST..	1A		YL951-YL999, YN232-YR328
2134B		24		Y2	HG	2-9	73-24-11	D41121J	B18			D10009B	B01			YC051-YD155
2134B		24		Y2	HG	3-10	73-24-11	D41121J	B18			D10135B	C04			YD157
2134B		24		Y2	HG	3-11	73-24-11	D41121J	B18			D10135B	C04			YD158-YR328
2134R		24		Y2	HG	0-0	73-24-11	D41121J	B17			D10009B	A01			YC051-YD155
2134R		24		Y2	HG	0-0	73-24-11	D41121J	B17			D10135B	B05			YD157-YR328
2134Z					HG	0-0	73-24-11	D41121J	PERG	1F		GB01110	ST..	1A		YC051-YD170, YN231
2134Z					HG	0-0	73-24-11	D41121J	PERG	1F		GB01105	ST..	1A		YL951-YL999, YN232-YR328
2135B		24		Y2	HH	6-4	73-24-21	D40063J	A08			D10009A	B07			YC051-YD155
2135B		24		Y2	HH	4-10	73-24-21	D40063J	A08			D10135A	J01			YD157-YR328
2135R		24		Y2	HH	0-0	73-24-21	D40063J	A07			D10009A	A07			YC051-YD155
2135R		24		Y2	HH	0-0	73-24-21	D40063J	A07			D10135A	J02			YD157-YR328
2135Z					HH	0-0	73-24-21	D40063J	PERG	1F		GB01110	ST..	1A		YC051-YD170, YN231
2135Z					HH	0-0	73-24-21	D40063J	PERG	1F		GB01105	ST..	1A		YL951-YL999, YN232-YR328
2136B		24		Y2	HI	5-5	73-24-21	D41157J	A06			D10009B	B07			YC051-YD155
2136B		24		Y2	HI	4-5	73-24-21	D41157J	A06			D10135B	D09			YD157-YR328
2136R		24		Y2	HI	0-0	73-24-21	D41157J	A05			D10009B	A07			YC051-YD155
2136R		24		Y2	HI	0-0	73-24-21	D41157J	A05			D10135B	C10			YD157-YR328
2136Z					HI	0-0	73-24-21	D41157J	PERG	1F		GB01110	ST..	1A		YC051-YD170, YN231
2136Z					HI	0-0	73-24-21	D41157J	PERG	1F		GB01105	ST..	1A		YL951-YL999, YN232-YR328
2139B		20		N2	EE	2-6	27-25-11	D10064	18			D45203J	B02			YC051-YD153
2139B		20		X2	EE	1-9	27-25-11	D10064	18			D45203J	B02			YD154-YR328
2139R		20		N2	EE	0-0	27-25-11	D10064	20			D45203J	B03			YC051-YD153
2139R		20		X2	EE	0-0	27-25-11	D10064	20			D45203J	B03			YD154-YR328
2139Z					EE	0-0	27-25-11	D10064	DED			D45203J	PERG	1F		ALL

WIRE LIST

D280A108

91-21-11

Section W0110

Page 37

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111		286A0111				E1-1 SHELF (continued)										
2140B		24		PL	HM	2-9	27-28-11	D41563J		B01		TB1101Y	B007	1A		ALL
2140R		24		PL	HM	0-0	27-28-11	D41563J		A10		TB1101Y	A007	1A		ALL
2141B		24		PL	HN	2-7	27-28-11	D40818J		A07		TB1101Y	B007	1A		ALL
2141R		24		PL	HN	0-0	27-28-11	D40818J		B08		TB1101Y	A007	1A		ALL
2142B		24		PL	HO	6-1	27-28-11	D10064		3		TB1101Y	B007	1A		YC051-YD157
2142B		24		PL	HO	6-2	27-28-11	D10064		3		TB1101Y	B007	1A		YD158-YR328
2142R		24		PL	HO	0-0	27-28-11	D10064		2		TB1101Y	A007	1A		ALL
2144B		24		PL	HQ	3-1	27-81-12	D40122J		A07		D00728A	J04			ALL
2144R		24		PL	HQ	0-0	27-81-12	D40122J		B07		D00728A	K04			ALL
2145B		24		PL	HR	3-1	27-81-12	D40122J		A06		D00728A	J05			ALL
2145R		24		PL	HR	0-0	27-81-12	D40122J		B06		D00728A	K05			ALL
2146B		24		PL	HS	3-1	27-81-12	D40122J		A08		D00728A	J06			ALL
2146R		24		PL	HS	0-0	27-81-12	D40122J		B08		D00728A	K06			ALL
2147B		24		PL	HT	3-1	27-81-12	D40122J		A02		D00728A	J07			ALL
2147R		24		PL	HT	0-0	27-81-12	D40122J		B02		D00728A	K07			ALL
2148B		24		PL	HU	3-1	27-81-12	D40122J		A01		D00728A	J08			ALL
2148R		24		PL	HU	0-0	27-81-12	D40122J		B01		D00728A	K08			ALL
2149B		24		PL	HV	3-1	27-81-12	D40122J		A03		D00728A	J09			ALL
2149R		24		PL	HV	0-0	27-81-12	D40122J		B03		D00728A	K09			ALL
2150B		24		PL	HW	3-1	27-81-12	D40122J		A04		D00728A	J10			ALL
2150R		24		PL	HW	0-0	27-81-12	D40122J		B04		D00728A	K10			ALL
2151B		24		PL	HX	3-1	27-81-12	D40122J		A05		D00728A	J11			ALL
2151R		24		PL	HX	0-0	27-81-12	D40122J		B05		D00728A	K11			ALL
2152B		24		PL	HY	4-5	27-81-21	D40160J		A01		D00728A	G13			ALL
2152R		24		PL	HY	0-0	27-81-21	D40160J		B01		D00728A	H13			ALL
2153B		24		PL	HZ	4-5	27-81-21	D40160J		A02		D00728A	G12			ALL
2153R		24		PL	HZ	0-0	27-81-21	D40160J		B02		D00728A	H12			ALL
2154B		24		PL	IA	4-5	27-81-21	D40160J		A03		D00728A	G14			ALL
2154R		24		PL	IA	0-0	27-81-21	D40160J		B03		D00728A	H14			ALL
2155B		24		PL	IB	4-5	27-81-21	D40160J		A04		D00728A	G15			ALL
2155R		24		PL	IB	0-0	27-81-21	D40160J		B04		D00728A	H15			ALL
2156B		24		PL	IC	4-9	27-81-22	D40142J		A07		D00728A	G10			ALL
2156R		24		PL	IC	0-0	27-81-22	D40142J		B07		D00728A	H10			ALL
2157B		24		PL	ID	4-9	27-81-22	D40142J		A06		D00728A	G11			ALL
2157R		24		PL	ID	0-0	27-81-22	D40142J		B06		D00728A	H11			ALL
2158B		24		PL	IE	4-9	27-81-22	D40142J		A08		D00728A	G08			ALL
2158R		24		PL	IE	0-0	27-81-22	D40142J		B08		D00728A	H08			ALL
2159B		24		PL	IF	4-9	27-81-22	D40142J		A02		D00728A	G09			ALL
2159R		24		PL	IF	0-0	27-81-22	D40142J		B02		D00728A	H09			ALL

WIRE LIST

D280A108

91-21-11

Section W0110

Page 38

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111			E1-1 SHELF (continued)											
2160B	24	PL	IG		4-9	27-81-22	D40142J	A01			D00728A	G06			ALL
2160R	24	PL	IG		0-0	27-81-22	D40142J	B01			D00728A	H06			ALL
2161B	24	PL	IH		4-9	27-81-22	D40142J	A03			D00728A	G07			ALL
2161R	24	PL	IH		0-0	27-81-22	D40142J	B03			D00728A	H07			ALL
2162B	24	PL	II		4-9	27-81-22	D40142J	A04			D00728A	G04			ALL
2162R	24	PL	II		0-0	27-81-22	D40142J	B04			D00728A	H04			ALL
2164B	24	PL	IK		4-9	27-81-22	D40142J	A05			D00728A	G05			ALL
2164R	24	PL	IK		0-0	27-81-22	D40142J	B05			D00728A	H05			ALL
2165B	24	Y2	IL		3-11	27-81-41	D00728B	C05			D10064	10			ALL
2165R	24	Y2	IL		0-0	27-81-41	D00728B	C04			D10064	9			ALL
2165Z			IL		0-0	27-81-41	D00728B	PERG	1A		D10064	DED			ALL
2168B	24	Y2	IO		3-2	27-81-41	D43211J	B16			D00728B	D05			ALL
2168R	24	Y2	IO		0-0	27-81-41	D43211J	A16			D00728B	D04			ALL
2168Z			IO		0-0	27-81-41	D43211J	PERG	1F		D00728B	PERG	1A		ALL
2169B	24	Y2	IP		3-5	31-22-11	D40019J	B16			D42311J	B08			YC051-YD157
2169B	24	Y2	IP		3-6	31-22-11	D40019J	B16			D42311J	B08			YD158-YR328
2169R	24	Y2	IP		0-0	31-22-11	D40019J	B15			D42311J	A08			ALL
2169Z			IP		0-0	31-22-11	D40019J	PERG	1F		D42311J	PERG	1F		ALL
2170B	24	Y2	IQ		3-5	31-22-11	D40019J	B14			D42311J	B07			YC051-YD157
2170B	24	Y2	IQ		3-6	31-22-11	D40019J	B14			D42311J	B07			YD158-YR328
2170R	24	Y2	IQ		0-0	31-22-11	D40019J	B13			D42311J	A07			ALL
2170Z			IQ		0-0	31-22-11	D40019J	PERG	1F		D42311J	PERG	1F		ALL
2171B	24	Y2	IR		3-1	22-11-51	D41145J	B04			TB1110Z	B017	1A		YC051-YD157
2171B	24	Y2	IR		4-3	22-11-51	D41145J	B04			TB1110Z	B017	1A		YD158-YR328
2171R	24	Y2	IR		0-0	22-11-51	D41145J	B03			TB1110Z	A017	1A		ALL
2171Z			IR		0-0	22-11-51	D41145J	PERG	1F		GB01110	ST..	1A		ALL
2175B	24	M5	IV		4-9	34-45-21	D02743E	G03			D46461J	A15			ALL
2175R	24	M5	IV		0-0	34-45-21	D02743E	F03			D46461J	A14			ALL
2175ZI			IV		0-0	34-45-21	D02743E	DED			D46461J	A16			ALL
2175ZO			IV		0-0	34-45-21	GB01103	ST..	1A		D46461J	PERG	1F		ALL
2176B	22	PB	FF		3-1	31-31-14	D04075J	B17			D42311J	A01			ALL
2176R	22	PB	FF		0-0	31-31-14	D04075J	B16			D42311J	A02			ALL
2177B	22	PB	FG		3-1	31-31-14	D04075J	A18			D42311J	A03			ALL
2177R	22	PB	FG		0-0	31-31-14	D04075J	A17			D42311J	A04			ALL
2179B	24	PL	FI		3-1	27-81-12	D40122J	B11			D00728A	A15			ALL
2179R	24	PL	FI		0-0	27-81-12	D40122J	A11			D00728A	A14			ALL
2180B	24	PL	FJ		3-1	27-81-12	D40122J	B12			D00728A	B15			ALL
2180R	24	PL	FJ		0-0	27-81-12	D40122J	A12			D00728A	B14			ALL
2181B	24	PL	FK		3-1	27-81-12	D40122J	B13			D00728A	C15			ALL

WIRE LIST

D280A108

91-21-11

Section W0110

Page 39

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111		286A0111			E1-1 SHELF (continued)											
2181R		24		PL	FK	0-0	27-81-12	D40122J	A13			D00728A	C14			ALL
2182B		24		PL	FL	4-9	27-81-22	D40948J	B01			D00728A	D15			ALL
2182R		24		PL	FL	0-0	27-81-22	D40948J	A01			D00728A	D14			ALL
2184B		24		PL	KA	4-2	27-81-11	D00728A	J13			D40120J	A04			ALL
2184R		24		PL	KA	0-0	27-81-11	D00728A	K13			D40120J	B04			ALL
2185B		24		PL	KB	4-2	27-81-11	D00728A	J12			D40120J	A05			ALL
2185R		24		PL	KB	0-0	27-81-11	D00728A	K12			D40120J	B05			ALL
2186B		24		PL	KC	4-2	27-81-11	D00728A	J14			D40120J	A06			ALL
2186R		24		PL	KC	0-0	27-81-11	D00728A	K14			D40120J	B06			ALL
2187B		24		PL	KD	4-2	27-81-11	D00728A	J15			D40120J	A07			ALL
2187R		24		PL	KD	0-0	27-81-11	D00728A	K15			D40120J	B07			ALL
2188B		20		X2	KE	5-0	27-52-11	D40180J	B10			TB1105Z	A013	1A		ALL
2188R		20		X2	KE	0-0	27-52-11	D40180J	A10			TB1105Z	A009	1A		ALL
2188Z					KE	0-0	27-52-11	D40180J	B09			TB1105Z	B013	1A		ALL
2189B		24		Y2	KF	4-2	27-52-11	D40180J	B08			D00728B	J08			ALL
2189R		24		Y2	KF	0-0	27-52-11	D40180J	A08			D00728B	J07			ALL
2189Z					KF	0-0	27-52-11	D40180J	A09			D00728B	DED			ALL
2190B		24		Y2	KG	3-10	27-52-11	D00728B	K11			D40019J	B18			ALL
2190R		24		Y2	KG	0-0	27-52-11	D00728B	K10			D40019J	B17			ALL
2190Z					KG	0-0	27-52-11	D00728B	DED			D40019J	A17			ALL
2191B		24		Y2	KH	3-10	27-52-11	D00728B	J11			D40019J	B03			ALL
2191R		24		Y2	KH	0-0	27-52-11	D00728B	J10			D40019J	B02			ALL
2191Z					KH	0-0	27-52-11	D00728B	DED			D40019J	B04			ALL
2192B		24		Y2	KJ	4-1	27-52-11	D00728B	K08			D40162J	B08			ALL
2192R		24		Y2	KJ	0-0	27-52-11	D00728B	K07			D40162J	A08			ALL
2192Z					KJ	0-0	27-52-11	D00728B	DED			D40162J	A09			ALL
2193B		20		X2	KK	4-11	27-52-11	D40162J	B10			TB1105Z	A013	1A		ALL
2193R		20		X2	KK	0-0	27-52-11	D40162J	A10			TB1105Z	B009	1A		ALL
2193Z					KK	0-0	27-52-11	D40162J	B09			TB1105Z	B013	1A		ALL
2197B		24		Y2	KO	2-10	34-61-22	D41155J	B16			D00235B	63			ALL
2197R		24		Y2	KO	0-0	34-61-22	D41155J	B15			D00235B	66			ALL
2197Z					KO	0-0	34-61-22	D41155J	PERG	1F		D00235B	DED			ALL
2198B		24		Y2	KP	2-10	34-61-22	D41155J	B08			D00235B	36			ALL
2198R		24		Y2	KP	0-0	34-61-22	D41155J	B07			D00235B	68			ALL
2198Z					KP	0-0	34-61-22	D41155J	PERG	1F		D00235B	DED			ALL
2199B		24		Y2	KQ	2-10	34-61-22	D41155J	A08			D00235B	48			ALL
2199R		24		Y2	KQ	0-0	34-61-22	D41155J	A07			D00235B	67			ALL
2199Z					KQ	0-0	34-61-22	D41155J	PERG	1F		D00235B	DED			ALL
2201B		24		PL	KR	4-9	27-81-22	D40948J	B02			D00728A	E15			ALL

WIRE LIST

D280A108

91-21-11

Section W0110

Page 40

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111			E1-1 SHELF (continued)											
2201R	24	PL	KR		0-0	27-81-22	D40948J	A02			D00728A	E14			ALL
2202B	24	PL	KS		4-9	27-81-22	D40948J	B03			D00728A	F15			ALL
2202R	24	PL	KS		0-0	27-81-22	D40948J	A03			D00728A	F14			ALL
2203B	24	Y2	KT		1-8	34-61-18	D43211J	A20			D40454J	B04			YC051-YC058
2203B	24	Y2	KT		1-8	31-32-15	D43211J	A20			D40454J	B04			YC059-YR328
2203R	24	Y2	KT		0-0	34-61-18	D43211J	A19			D40454J	A04			YC051-YC058
2203R	24	Y2	KT		0-0	31-32-15	D43211J	A19			D40454J	A04			YC059-YR328
2203Z			KT		0-0	34-61-18	D43211J	PERG	1A		D40454J	PERG	1A		YC051-YC058
2203Z			KT		0-0	31-32-15	D43211J	PERG	1F		D40454J	PERG	1F		YC059-YR328
2204B	24	7K	KU		2-9	34-49-11	D40454J	A06			D01153A	D03			YC053-YD157
2204B	24	7K	KU		2-10	34-49-11	D40454J	A06			D01153A	D03			YD158-YR328
2204W	24	7K	KU		0-0	34-49-11	D40454J	A05			D01153A	C03			YC053-YR328
2204Z			KU		0-0	34-49-11	D40454J	PERG	1F		D01153A	PERG	1A		YC053-YR328
2205B	24	Y2	KV		2-9	34-49-11	D40454J	B09			D01153A	D08			YC053-YD157
2205B	24	Y2	KV		2-10	34-49-11	D40454J	B09			D01153A	D08			YD158-YR328
2205R	24	Y2	KV		0-0	34-49-11	D40454J	B08			D01153A	C08			YC053-YR328
2205Z			KV		0-0	34-49-11	D40454J	PERG	1F		D01153A	PERG	1A		YC053-YR328
2206B	24	7K	KW		2-9	34-49-11	D40458J	A02			D01153A	B03			YC053-YD157
2206B	24	7K	KW		2-10	34-49-11	D40458J	A02			D01153A	B03			YD158-YR328
2206W	24	7K	KW		0-0	34-49-11	D40458J	A01			D01153A	A03			YC053-YR328
2206Z			KW		0-0	34-49-11	D40458J	PERG	1F		D01153A	PERG	1A		YC053-YR328
2207B	24	Y2	KX		2-11	34-21-23	D01153A	A06			TB1109Z	B009	1A		YC053-YD157
2207B	24	Y2	KX		4-2	34-21-23	D01153A	A06			TB1109Z	B009	1A		YD158-YR328
2207R	24	Y2	KX		0-0	34-21-23	D01153A	A05			TB1109Z	A009	1A		YC053-YR328
2207Z			KX		0-0	34-21-23	D01153A	PERG	1A		GB01109	ST..	1A		YC053-YR328
2208B	24	Y2	KY		6-5	34-21-24	D01153A	D01			D41147J	A04			YC053-YD157
2208B	24	Y2	KY		6-4	34-21-24	D01153A	D01			D41147J	A04			YD158-YR328
2208R	24	Y2	KY		0-0	34-21-24	D01153A	C01			D41147J	A03			YC053-YR328
2208Z			KY		0-0	34-21-24	D01153A	PERG	1A		D41147J	PERG	1F		YC053-YR328
2209B	24	Y2	KZ		2-11	34-58-11	D41125J	B02			D01153B	D06			YC053-YD157
2209B	24	Y2	KZ		3-1	34-58-11	D41125J	B02			D01153B	D06			YD158-YR328
2209R	24	Y2	KZ		0-0	34-58-11	D41125J	B01			D01153B	C06			YC053-YR328
2209Z			KZ		0-0	34-58-11	D41125J	PERG	1F		D01153B	PERG	1A		YC053-YR328
2210B	24	Y2	LA		6-6	34-58-21	D43317J	B04			D01153A	D11			YC053-YD157
2210B	24	Y2	LA		6-5	34-58-21	D43317J	B04			D01153A	D11			YD158-YR328
2210R	24	Y2	LA		0-0	34-58-21	D43317J	B03			D01153A	C11			YC053-YR328
2210Z			LA		0-0	34-58-21	D43317J	PERG	1F		D01153A	PERG	1A		YC053-YR328
2219B	24	Y2	LJ		4-10	22-11-53	D41153J	B01			D10135A	D06			YC059-YR328
2219R	24	Y2	LJ		0-0	22-11-53	D41153J	A01			D10135A	E06			YC059-YR328

WIRE LIST

D280A108

91-21-11

Section W0110

Page 41

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111	286A0111				E1-1 SHELF (continued)										
2219Z				LJ	0-0	22-11-53	D41153J	PERG	1F		GB01104	ST..	1A		YC059-YR328
2220B	22		X2	LK	4-0	31-32-15	D41155J	B11			TB1105Y	B017	1A		YC059-YR328
2220R	22		X2	LK	0-0	31-32-15	D41155J	B06			TB1105Y	A017	1A		YC059-YR328
2220Z				LK	0-0	31-32-15	D41155J	PERG	1F		GB01105	ST..	1A		YC059-YR328
2221B	22		X2	LL	1-11	31-32-15	D10135A	F06			TB1105Y	B017	1A		YC059-YR328
2221R	22		X2	LL	0-0	31-32-15	D10135A	G06			TB1105Y	A017	1A		YC059-YR328
2221Z				LL	0-0	31-32-15	GB01104	ST..	1A		GB01105	ST..	1A		YC059-YR328
2222B	22		X2	LM	4-1	31-32-15	D41145J	B02			TB1105Y	B017	1A		YC059-YD157
2222B	22		X2	LM	4-2	31-32-15	D41145J	B02			TB1105Y	B017	1A		YD158-YR328
2222R	22		X2	LM	0-0	31-32-15	D41145J	B01			TB1105Y	A017	1A		YC059-YR328
2222Z				LM	0-0	31-32-15	D41145J	PERG	1F		GB01105	ST..	1A		YC059-YR328
2223B	22		X2	GF	5-0	22-11-81	D10135B	J10			D45551J	B03			YD157-YR328
2223R	22		X2	GF	0-0	22-11-81	D10135B	K10			D45551J	A03			YD157-YR328
2223Z				GF	0-0	22-11-81	GB01104	ST..	1A		D45551J	PERG	1F		YD157-YD158
2223Z				GF	0-0	22-11-81	GB01105	ST..	1A		D45551J	PERG	1F		YL951-YR328
2224B	22		X2	GG	5-0	22-11-81	D10135B	H07			D45551J	B10			YD157-YR328
2224R	22		X2	GG	0-0	22-11-81	D10135B	H06			D45551J	A10			YD157-YR328
2224Z				GG	0-0	22-11-81	GB01104	ST..	1A		D45551J	PERG	1F		YD157-YD158
2224Z				GG	0-0	22-11-81	GB01105	ST..	1A		D45551J	PERG	1F		YL951-YR328
2225B	22		X2	GI	5-1	22-11-81	D10135A	G11			D45551J	B01			YD157-YR328
2225R	22		X2	GI	0-0	22-11-81	D10135A	F11			D45551J	A01			YD157-YR328
2225Z				GI	0-0	22-11-81	GB01104	ST..	1A		D45551J	PERG	1F		YD157-YR328
2226B	22		X2	GJ	4-10	22-11-81	TB1104Y	B001	1A		D45551J	B06			YD157-YR328
2226R	22		X2	GJ	0-0	22-11-81	TB1104Y	A001	1A		D45551J	A06			YD157-YR328
2226Z				GJ	0-0	22-11-81	GB01104	ST..	1A		D45551J	PERG	1F		YD157-YR328
2229B	22		X2	GP	4-9	22-12-31	D04079J	A20			TB1104Y	B001	1A		YD157-YR328
2229R	22		X2	GP	0-0	22-12-31	D04079J	A19			TB1104Y	A001	1A		YD157-YR328
2229Z				GP	0-0	22-12-31	D04079J	PERG	1F		GB01104	ST..	1A		YD157-YR328
2230B	24		Y2	GQ	3-8	22-11-51	D10135B	K04			TB1110Z	B005	1A		YD157
2230B	24		Y2	GQ	2-9	22-11-51	D10135B	K04			TB1110Z	B005	1A		YD158-YR328
2230R	24		Y2	GQ	0-0	22-11-51	D10135B	K05			TB1110Z	A005	1A		YD157-YR328
2230Z				GQ	0-0	22-11-51	GB01104	ST..	1A		GB01110	ST..	1A		YD157-YD158
2230Z				GQ	0-0	22-11-51	D10135B	DED			GB01110	ST..	1A		YL951-YR328
2241B	24		Y2	FH	1-11	21-31-24	D10740B	A04			TB1111Y	B001	1A		YD158-YR328
2241R	24		Y2	FH	0-0	21-31-24	D10740B	A03			TB1111Y	A001	1A		YD158-YR328
2241Z				FH	0-0	21-31-24	D10740B	PERG	1A		GB01111	ST..	1A		YD158-YR328
2242B	24		Y2	FY	3-11	21-31-24	D40774J	B05			TB1111Y	B001	1A		YD158-YR328
2242R	24		Y2	FY	0-0	21-31-24	D40774J	A05			TB1111Y	A001	1A		YD158-YR328
2242Z				FY	0-0	21-31-24	D40774J	PERG	1F		GB01111	ST..	1A		YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0110

Page 42

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111		286A0111			E1-1 SHELF (continued)											
2243B		24		Y2	FM	1-11	21-31-24	D10740B	A06			TB1111Y	B003	1A		YD158-YR328
2243R		24		Y2	FM	0-0	21-31-24	D10740B	A05			TB1111Y	A003	1A		YD158-YR328
2243Z					FM	0-0	21-31-24	D10740B	PERG	1A		GB01111	ST..	1A		YD158-YR328
2244B		24		Y2	GM	3-11	21-31-24	D40774J	B06			TB1111Y	B003	1A		YD158-YR328
2244R		24		Y2	GM	0-0	21-31-24	D40774J	A06			TB1111Y	A003	1A		YD158-YR328
2244Z					GM	0-0	21-31-24	D40774J	PERG	1F		GB01111	ST..	1A		YD158-YR328
2245B		24		Y2	FN	1-10	21-31-24	D10740B	A10			TB1111Y	B005	1A		YD158-YR328
2245R		24		Y2	FN	0-0	21-31-24	D10740B	A09			TB1111Y	A005	1A		YD158-YR328
2245Z					FN	0-0	21-31-24	D10740B	PERG	1A		GB01111	ST..	1A		YD158-YR328
2246B		24		Y2	GO	3-10	21-31-24	D40774J	B07			TB1111Y	B005	1A		YD158-YR328
2246R		24		Y2	GO	0-0	21-31-24	D40774J	A07			TB1111Y	A005	1A		YD158-YR328
2246Z					GO	0-0	21-31-24	D40774J	PERG	1F		GB01111	ST..	1A		YD158-YR328
2247B		24		Y2	FO	1-10	21-31-24	D10740B	A14			TB1111Y	B007	1A		YD158-YR328
2247R		24		Y2	FO	0-0	21-31-24	D10740B	A13			TB1111Y	A007	1A		YD158-YR328
2247Z					FO	0-0	21-31-24	D10740B	PERG	1A		GB01111	ST..	1A		YD158-YR328
2248B		24		Y2	GR	3-10	21-31-24	D40774J	B08			TB1111Y	B007	1A		YD158-YR328
2248R		24		Y2	GR	0-0	21-31-24	D40774J	A08			TB1111Y	A007	1A		YD158-YR328
2248Z					GR	0-0	21-31-24	D40774J	PERG	1F		GB01111	ST..	1A		YD158-YR328
2249B		24		Y2	GT	6-3	21-31-23	D40064J	B03			D10740B	A08			YD158-YR328
2249R		24		Y2	GT	0-0	21-31-23	D40064J	A03			D10740B	A07			YD158-YR328
2249Z					GT	0-0	21-31-23	D40064J	PERG	1F		D10740B	PERG	1A		YD158-YR328
2250B		24		Y2	GU	6-4	21-31-23	D40064J	B06			D10740A	A02			YD158-YR328
2250R		24		Y2	GU	0-0	21-31-23	D40064J	A06			D10740A	A01			YD158-YR328
2250Z					GU	0-0	21-31-23	D40064J	PERG	1F		D10740A	PERG	1A		YD158-YR328
2251B		24		Y2	GX	3-2	21-31-23	D42311J	A06			D10740A	A08			YD158-YR328
2251R		24		Y2	GX	0-0	21-31-23	D42311J	A05			D10740A	A07			YD158-YR328
2251Z					GX	0-0	21-31-23	D42311J	PERG	1F		D10740A	PERG	1A		YD158-YR328
2252B		24		Y2	GY	3-2	21-31-23	D42311J	B10			D10740A	A10			YD158-YR328
2252R		24		Y2	GY	0-0	21-31-23	D42311J	B09			D10740A	A09			YD158-YR328
2252Z					GY	0-0	21-31-23	D42311J	PERG	1F		D10740A	PERG	1A		YD158-YR328
2253B		24		Y2	GW	6-3	27-32-22	D40464J	B07			TB1111Y	B007	1A		YD158-YR328
2253R		24		Y2	GW	0-0	27-32-22	D40464J	A07			TB1111Y	A007	1A		YD158-YR328
2253Z					GW	0-0	27-32-22	D40464J	PERG	1F		GB01111	ST..	1A		YD158-YR328
2254B		24		Y2	HJ	2-11	27-32-12	D46461J	B01			TB1111Y	B003	1A		YD158-YR328
2254R		24		Y2	HJ	0-0	27-32-12	D46461J	A01			TB1111Y	A003	1A		YD158-YR328
2254Z					HJ	0-0	27-32-12	D46461J	PERG	1F		GB01111	ST..	1A		YD158-YR328
2255B		24		Y2	HK	3-8	34-21-14	D45203J	B08			TB1111Y	B001	1A		YD158-YR328
2255R		24		Y2	HK	0-0	34-21-14	D45203J	B07			TB1111Y	A001	1A		YD158-YR328
2255Z					HK	0-0	34-21-14	D45203J	PERG	1F		GB01111	ST..	1A		YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0110

Page 43

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W0111	286A0111	E1-1 SHELF (continued)			
2256B	24 Y2 HL	5-3 34-21-24	D41147J B08	TB1111Y B005 1A	YD158-YR328
2256R	24 Y2 HL	0-0 34-21-24	D41147J B06	TB1111Y A005 1A	YD158-YR328
2256Z	HL	0-0 34-21-24	D41147J PERG 1F	GB01111 ST.. 1A	YD158-YR328
2284B	24 Y2 KN	6-6 31-35-04	D41563J B05	D10740A A06	YL963-YL999, YN236-YR328
2284R	24 Y2 KN	0-0 31-35-04	D41563J A05	D10740A A05	YL963-YL999, YN236-YR328
2284Z	KN	0-0 31-35-04	D41563J PERG 1F	D10740A PERG 1A	YL963-YL999, YN236-YR328
2333B	24 Y2 GA	4-1 22-11-51	D10135B A08	D43211J B20	ALL
2333R	24 Y2 GA	0-0 22-11-51	D10135B B08	D43211J B19	ALL
2333Z	GA	0-0 22-11-51	D10135B DED	D43211J PERG 1F	YC051-YC052
2333Z	GA	0-0 22-11-51	GB01104 ST.. 1A	D43211J PERG 1F	YC053-YD158
2333Z	GA	0-0 22-11-51	GB01105 ST.. 1A	D43211J PERG 1F	YL951-YR328
2334B	24 Y2 GB	3-3 22-23-12	D45113J B08	D10064 23	ALL
2334R	24 Y2 GB	0-0 22-23-12	D45113J A08	D10064 22	ALL
2334Z	GB	0-0 22-23-12	D45113J PERG 1F	D10064 DED	ALL
2335B	24 Y2 GC	7-6 22-23-12	D41563J B07	D10064 13	ALL
2335R	24 Y2 GC	0-0 22-23-12	D41563J B06	D10064 12	ALL
2335Z	GC	0-0 22-23-12	D41563J PERG 1F	D10064 DED	ALL
2508B	24 Y2 BU	1-10 31-62-11	D45203J B09	SM00097 W	YC051-YD153
2508B	24 Y2 BU	1-9 31-62-11	D45203J B09	SM00097 W	YD154-YD157
2508R	24 Y2 BU	0-0 31-62-11	D45203J A09	SM00095 W	YC051-YD157
2508Z	BU	0-0 31-62-11	D45203J PERG 1F	SM00099 W	YC051-YD157
2509B	24 Y2 BV	1-9 31-62-11	D04069J B14	SM00097 W	YC051-YD153
2509B	24 Y2 BV	1-8 31-62-11	D04069J B14	SM00097 W	YD154-YD157
2509R	24 Y2 BV	0-0 31-62-11	D04069J B13	SM00095 W	YC051-YD157
2509Z	BV	0-0 31-62-11	D04069J PERG 1F	SM00099 W	YC051-YD157
3001B	22 X3 FA	4-5 22-11-31	D10135B J13	D04073J A13	ALL
3001R	22 X3 FA	0-0 22-11-31	D10135B K13	D04073J A12	ALL
3001Y	22 X3 FA	0-0 22-11-31	D10135B H13	D04073J A14	ALL
3001Z	FA	0-0 22-11-31	D10135B DED	D04073J PERG 1F	YC051-YC052
3001Z	FA	0-0 22-11-31	GB01104 ST.. 1A	D04073J PERG 1F	YC053-YD158
3001Z	FA	0-0 22-11-31	GB01105 ST.. 1A	D04073J PERG 1F	YL951-YR328
3002B	22 X3 FB	4-5 22-11-31	D10135B G15	D04073J A16	ALL
3002R	22 X3 FB	0-0 22-11-31	D10135B J15	D04073J A15	ALL
3002Y	22 X3 FB	0-0 22-11-31	D10135B H15	D04073J A17	ALL
3002Z	FB	0-0 22-11-31	D10135B DED	D04073J PERG 1F	YC051-YC052
3002Z	FB	0-0 22-11-31	GB01104 ST.. 1A	D04073J PERG 1F	YC053-YD158

WIRE LIST

D280A108

91-21-11

Section W0110

Page 44

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To
Wire No.	GA CO TY	Fam FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice Effectivity
W0111	286A0111	E1-1 SHELF (continued)		
3002Z		FB 0-0 22-11-31	GB01105 ST.. 1A	D04073J PERG 1F YL951-YR328
3003B	22 X3	FC 4-5 22-12-31	D10135B F06	D04073J A19 ALL
3003R	22 X3	FC 0-0 22-12-31	D10135B G06	D04073J A18 ALL
3003Y	22 X3	FC 0-0 22-12-31	D10135B E06	D04073J A20 ALL
3003Z		FC 0-0 22-12-31	GB01104 ST.. 1A	D04073J PERG 1F YC051-YD158
3003Z		FC 0-0 22-12-31	GB01105 ST.. 1A	D04073J PERG 1F YL951-YR328
3004B	22 X3	FD 5-0 22-12-31	D10135A J13	D04079J A17 ALL
3004R	22 X3	FD 0-0 22-12-31	D10135A K13	D04079J A16 ALL
3004Y	22 X3	FD 0-0 22-12-31	D10135A H13	D04079J A18 ALL
3004Z		FD 0-0 22-12-31	D10135A DED	D04079J PERG 1F YC051-YC052
3004Z		FD 0-0 22-12-31	GB01104 ST.. 1A	D04079J PERG 1F YC053-YR328
3005B	22 X3	FE 5-0 22-12-31	D10135A G15	D04079J A13 ALL
3005R	22 X3	FE 0-0 22-12-31	D10135A J15	D04079J A12 ALL
3005Y	22 X3	FE 0-0 22-12-31	D10135A H15	D04079J A14 ALL
3005Z		FE 0-0 22-12-31	D10135A DED	D04079J PERG 1F YC051-YC052, YL951-YR328
3005Z		FE 0-0 22-12-31	GB01104 ST.. 1A	D04079J PERG 1F YC053-YD170
3010B	22 X3	GK 5-1 22-11-81	D10135A G09	D45551J B07 YD157-YR328
3010R	22 X3	GK 0-0 22-11-81	D10135A H09	D45551J A07 YD157-YR328
3010Y	22 X3	GK 0-0 22-11-81	D10135A G10	D45551J A08 YD157-YR328
3010Z		GK 0-0 22-11-81	GB01104 ST.. 1A	D45551J PERG 1F YD157-YR328
3016B	22 PC	FP 4-1 27-53-21	D00728B E14	D40162J A05 ALL
3016R	22 PC	FP 0-0 27-53-21	D00728B E13	D40162J A04 ALL
3016Y	22 PC	FP 0-0 27-53-21	D00728B E15	D40162J A06 ALL
3017B	22 PC	FQ 4-1 27-53-21	D00728B F14	D40162J A02 ALL
3017R	22 PC	FQ 0-0 27-53-21	D00728B F13	D40162J A01 ALL
3017Y	22 PC	FQ 0-0 27-53-21	D00728B F15	D40162J A03 ALL
3018B	22 PC	FR 4-1 27-53-21	D00728B G14	D40162J B05 ALL
3018R	22 PC	FR 0-0 27-53-21	D00728B G13	D40162J B04 ALL
3018Y	22 PC	FR 0-0 27-53-21	D00728B G15	D40162J B06 ALL
3019B	22 PC	FS 4-1 27-53-21	D00728B H14	D40162J B02 ALL
3019R	22 PC	FS 0-0 27-53-21	D00728B H13	D40162J B01 ALL
3019Y	22 PC	FS 0-0 27-53-21	D00728B H15	D40162J B03 ALL
3020B	22 PC	FT 4-2 27-53-21	D00728B D14	D40180J A05 ALL
3020R	22 PC	FT 0-0 27-53-21	D00728B D13	D40180J A04 ALL
3020Y	22 PC	FT 0-0 27-53-21	D00728B D15	D40180J A06 ALL
3021B	22 PC	FU 4-2 27-53-21	D00728B C14	D40180J A02 ALL
3021R	22 PC	FU 0-0 27-53-21	D00728B C13	D40180J A01 ALL
3021Y	22 PC	FU 0-0 27-53-21	D00728B C15	D40180J A03 ALL

WIRE LIST

D280A108

91-21-11

Section W0110

Page 45

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0111		286A0111					E1-1 SHELF (continued)									
3022B		22		PC	FV	4-2	27-53-21	D00728B		B14		D40180J		B05		ALL
3022R		22		PC	FV	0-0	27-53-21	D00728B		B13		D40180J		B04		ALL
3022Y		22		PC	FV	0-0	27-53-21	D00728B		B15		D40180J		B06		ALL
3023B		22		PC	FW	4-2	27-53-21	D00728B		A14		D40180J		B02		ALL
3023R		22		PC	FW	0-0	27-53-21	D00728B		A13		D40180J		B01		ALL
3023Y		22		PC	FW	0-0	27-53-21	D00728B		A15		D40180J		B03		ALL
3024B		22		PC	FX	4-8	27-51-11	D40818J		B02		D00728B		A11		ALL
3024R		22		PC	FX	0-0	27-51-11	D40818J		A02		D00728B		A10		ALL
3024Y		22		PC	FX	0-0	27-51-11	D40818J		B03		D00728B		A12		ALL
3026B		22		PC	FZ	3-1	31-31-14	D42311J		B02		D04075J		A08		ALL
3026R		22		PC	FZ	0-0	31-31-14	D42311J		B01		D04075J		A07		ALL
3026Y		22		PC	FZ	0-0	31-31-14	D42311J		B03		D04075J		A09		ALL
3027B		22		PC	MA	3-1	31-31-14	D42311J		B05		D04075J		B19		ALL
3027R		22		PC	MA	0-0	31-31-14	D42311J		B04		D04075J		B18		ALL
3027Y		22		PC	MA	0-0	31-31-14	D42311J		B06		D04075J		B20		ALL
3028B		20		X3	MB	4-8	27-52-11	D40019J		B08		TB1105Z	A013	1A		ALL
3028R		20		X3	MB	0-0	27-52-11	D40019J		B07		TB1105Z	A009	1A		ALL
3028Y		20		X3	MB	0-0	27-52-11	D40019J		B09		TB1105Z	B009	1A		ALL
3028Z					MB	0-0	27-52-11	D40019J		B12		TB1105Z	B013	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0110

Page 46 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Fam	Description FT-IN Diagram		From Equip Term Type Splice				To Equip Term Type Splice Effectivity				
W0121	286A0121				E1-2 SHELF										
0001	20	CQ			1-6 34-53-11	D00149C		1				TB1202Y	A001	1A	ALL
0002	20	CQ			6-4 34-53-11	D41827P		4				TB1202Y	A001	1A	ALL
0003	20	CQ			6-0 34-53-11	D41217P		3				TB1202Y	A001	1A	ALL
0004	20	PA			2-1 34-53-11	D00149C		7				GD01203	AC..	1A	ALL
0006	20	PA			2-1 34-53-11	D00149C		11				GD01203	ST..	1A	ALL
0007	24	PK			6-4 34-53-11	D41217P		7				D00149A	G07		ALL
0008	20	PA			2-1 34-53-11	D00149C		8				GD01203	DC..	1A	ALL
0009	20	PA			5-5 34-53-11	D41217P		9				GD01203	ST..	1A	ALL
0010	20	PA			5-5 34-53-11	D41217P		10				GD01203	ST..	1A	ALL
0011	24	PK			6-4 34-53-11	D41217P		11				D00149A	K05		ALL
0012	24	PK			6-4 34-53-11	D41217P		12				D00149A	B03		ALL
0015	24	PK			6-4 34-53-11	D41217P		15				D00149A	J05		ALL
0016	24	PK			6-3 34-53-11	D41217P		6				D00149B	E06		ALL
0017	24	PK			0-7 34-53-11	D00149A		H03				D00149A	J03		ALL
0018	22	PA			2-6 34-55-11	D00161C		11				GD01203	ST..	1A	ALL
0019	22	PA			2-3 34-55-11	D00161C		7				GD01204	AC..	1A	ALL
001CO				BA	0-0 34-53-31	D00149A		= C71				D04603P	= C1		ALL
001CX		0J		BA	3-6 34-53-31	D00149A		71				D04603P	= A1		ALL
0020	24	PK			6-3 34-53-11	D41217P		1				D00149B	K03		ALL
0021	22	GA			5-5 34-55-11	D00161C		1				D41211P	41		YC051-YC052
0021	22	PA			6-10 34-55-11	D00161C		1				D41827P	8		YC053-YD170
0021	22	CQ			6-10 34-55-11	D00161C		1				D41827P	8		YL951-YR328
0024	24	PK			2-4 34-53-11	D41217P		2				D04029P	22		ALL
0025	20	PA			5-5 34-53-11	D41217P		5				GD01203	ST..	1A	ALL
0026	22	PA			6-9 34-55-11	D00161B		K05				D04029P	13		ALL
0028	22	PA			6-0 34-55-11	D04029P		3				GD01203	DC..	1A	ALL
0029	22	PA			2-8 34-55-11	D00161B		A05				GD01203	ST..	1A	ALL
002CO				BB	0-0 34-53-31	D00149C		= C12				D02477	= C1		ALL
002CX		0F		BB	0-8 34-53-31	D00149C		12	DN			D02477	= A1		ALL
0030	22	CQ			1-9 34-51-41	D45201P		11				D04029P	51		YC051-YD158
0030	22	CQ			6-1 34-51-41	D45201P		11				TB1201Y	B017	1A	YL951-YR328
0031	22	CQ			2-3 34-51-41	D45201P		7				D04029P	31		ALL
0032	22	PA			6-9 34-55-11	D00161B		B05				D04029P	6		ALL
0034	22	CQ			5-3 34-31-11	D10719C		9				D41827P	7		ALL
0035	20	CQ			1-7 34-31-11	D10719C		7				GD01202	AC..	1A	ALL
0036	20	CQ			1-11 34-31-11	D10719C		8				GD01201	ST..	1A	YC051-YD170
0036	20	PA			1-11 34-31-11	D10719C		8				GD01201	ST..	1A	YL951-YR328
0037	22	PA			4-6 34-31-11	D10719B		A04				D41211P	49		ALL
0039	22	G5			2-4 22-11-18	D10719B		F15				TB1201Y	A015	1A	ALL

WIRE LIST

D280A108

91-21-11

Section W0120

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To
Wire No.	GA CO TY	Fam FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice Effectivity
W0121	286A0121	E1-2 SHELF (continued)		
003CO		BC 0-0 34-53-31	D02473 =C1	D10163 =C1 ALL
003CX		0F BC 2-8 34-53-31	D02473 =A1	D10163 =A1 YC051-YD170
003CX		0F BC 2-9 34-53-31	D02473 =A1	D10163 =A1 YL951-YR328
0040	22	G5 5-0 22-11-18	D45115P 1	TB1201Y A015 1A ALL
0041	22	CQ 5-5 34-51-11	D03623C 2	D41827P 5 ALL
0042	20	CQ 1-10 34-51-11	D03623C 3	GD01201 AC.. 1A ALL
0043	20	CQ 1-10 34-51-11	D03623C 4	GD01201 ST.. 1A ALL
0044	22	CQ 2-7 34-51-11	D41827P 6	D04029P 54 ALL
0045	22	PA 4-10 34-51-11	D03623B A15	D45115P 2 ALL
004CO		BD 0-0 34-53-31	D00149B =C71	D04607P =C1 ALL
004CX		0G BD 3-5 34-53-31	D00149B 71	D04607P =A1 ALL
0050	22	PA 2-3 34-53-11	GD01203 DC.. %A	D00149B G05 YD158-YR328
0052	22	CQ 2-3 34-51-41	D45201P 2	D04029P 12 ALL
0053	22	CQ 2-0 34-51-41	D45201P 1	D41827P 14 ALL
0054	22	CQ 6-1 34-51-41	D04029P 38	TB1201Y B015 1A ALL
0055	22	CQ 6-0 34-51-41	D45201P 5	TB1201Y B015 1A ALL
0056	22	CQ 4-8 34-51-41	D41127P 2	TB1201Y B015 1A ALL
0058	22	PA 3-0 34-21-15	D04205P 7	D41127P 8 ALL
0059	22	PA 3-4 23-51-51	D04029P 15	D45115P 55 ALL
005CO		BE 0-0 34-55-11	D00161C =C12	D02475 =C1 ALL
005CX		0F BE 0-8 34-55-11	D00161C 12 DN	D02475 =A1 ALL
0065	22	G5 5-0 22-11-18	D45115P 10	TB1201Y A015 1A ALL
0066	22	G5 6-1 22-11-18	D04029P 5	TB1201Y A015 1A ALL
0067	22	G5 2-4 22-11-18	D45115P 53	D41127P 1 ALL
0068	20	CQ 2-0 22-14-11	D41827P 13	D45201P 3 ALL
0069	24	PK 1-9 34-53-11	D00149A C03	TB1202Y A003 1A ALL
006CO		BF 0-0 34-55-11	D00161B =C71	D41215P =C1 ALL
006CX		0H BF 4-0 34-55-11	D00161B 71	D41215P =A1 ALL
0070	24	PK 1-9 34-53-11	D00149A E03	TB1202Y A003 1A ALL
0071	24	PK 1-9 34-53-11	D00149A F03	TB1202Y A003 1A ALL
0073	24	PK 2-5 34-31-11	D10719B B05	TB1201Y A017 1A YC051-YD170
0074	24	PK 2-5 34-31-11	D10719B H04	TB1201Y A017 1A ALL
0075	24	PK 2-5 34-31-11	D10719B K04	TB1201Y A017 1A ALL
0076	24	PK 3-6 22-11-53	D41251P 21	D45115P 4 YC059-YR328
0077	24	PK 3-6 22-11-53	D41251P 22	D45115P 6 YC059-YR328
0078	24	PK 3-6 22-11-53	D41251P 23	D45115P 7 YC059-YR328
0079	24	PK 3-6 22-11-53	D41251P 24	D45115P 8 YC059-YR328
007CO		BG 0-0 34-32-11	D03623C =C5	D04121P =C1 ALL
007CX		0F BG 3-0 34-32-11	D03623C 5 DN	D04121P =A1 ALL

WIRE LIST

D280A108

91-21-11

Section W0120

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0121	286A0121				E1-2 SHELF (continued)										
0086	22		CQ		6-2	34-51-41	D04029P	11			TB1201Y	B017	1A		YL951-YR328
0087	22		CQ		6-2	34-51-41	D04029P	51			TB1201Y	B017	1A		YL951-YR328
0088	22		CQ		2-3	34-51-41	D45201P	17			D04029P	10			YL951-YR328
0089	22		PA		1-10	34-31-11	D10719B	D05			GD01202	DC..	1A		YL951-YR328
008CO				BH	0-0	34-31-11	D10719C	= C13			D04025P	= C1			ALL
008CX			OF	BH	2-9	34-31-11	D10719C	13	DN		D04025P	= A1			ALL
0090	22		PA		1-10	34-31-11	D10719B	D07			GD01202	DC..	1A		YL951-YR328
0091	22		PA		1-10	34-31-11	D10719B	H05			GD01202	DC..	1A		YL951-YR328
0092	22		PA		1-10	34-31-11	D10719B	J05			GD01202	DC..	1A		YL951-YR328
0094	24		PK		2-0	31-31-15	D45002P	3			D41217P	51			YL963-YL999, YN236-YR328
0095	24		PK		2-0	31-31-15	D45002P	4			D41217P	52			YL963-YL999, YN236-YR328
009CO				BJ	0-0	34-31-11	D10719C	= C12			D02115	= C1			ALL
009CX			OF	BJ	2-2	34-31-11	D10719C	12	DN		D02115	= A1			ALL
010CO				BK	0-0	34-51-11	D03623C	= C1			D03781	= C1			ALL
010CX			OF	BK	2-2	34-51-11	D03623C	1	DN		D03781	= A1			ALL
011CO				BL	0-0	34-58-11	D42941P	= C1			D10719A	= C2			ALL
011CX			OF	BL	3-4	34-58-11	D42941P	= A1			D10719A	2			YC051-YL999, YR301-YR328
011CX			OF	BL	3-0	34-58-11	D42941P	= A1			D10719A	2			YN231-YN501
0201	24		PK		5-2	34-53-11	D00149B	A01			D41211P	1			ALL
0202	24		PK		5-2	34-53-11	D00149B	B01			D41211P	2			ALL
0203	24		PK		5-2	34-53-11	D00149B	C01			D41211P	3			ALL
0204	24		PK		5-2	34-53-11	D00149B	D01			D41211P	4			ALL
0205	24		PK		5-2	34-53-11	D00149B	E01			D41211P	5			ALL
0206	24		PK		5-2	34-53-11	D00149B	F01			D41211P	6			ALL
0207	24		PK		5-2	34-53-11	D00149B	G01			D41211P	7			ALL
0208	24		PK		5-2	34-53-11	D00149B	H01			D41211P	8			ALL
0209	24		PK		5-2	34-53-11	D00149B	J01			D41211P	9			ALL
0210	24		PK		5-2	34-53-11	D00149B	K01			D41211P	10			ALL
0211	24		PK		5-2	34-53-11	D00149B	A02			D41211P	11			ALL
0212	24		PK		5-2	34-53-11	D00149B	B02			D41211P	12			ALL
0213	24		PK		5-2	34-53-11	D00149B	C02			D41211P	13			ALL
0214	24		PK		5-2	34-53-11	D00149B	D02			D41211P	14			ALL
0215	24		PK		5-2	34-53-11	D00149B	E02			D41211P	15			ALL
0216	24		PK		5-2	34-53-11	D00149B	F02			D41211P	16			ALL
0217	24		PK		5-2	34-53-11	D00149B	G02			D41211P	17			ALL
0218	24		PK		5-2	34-53-11	D00149B	H02			D41211P	18			ALL

WIRE LIST

D280A108

91-21-11

Section W0120

Page 3

Nov 12/2012

Bundle No.	Part Number			Fam	Description		From				To				
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0121	286A0121				E1-2 SHELF (continued)										
0219	24		PK		5-2	34-53-11	D00149B	J02			D41211P	19			ALL
0220	24		PK		5-2	34-53-11	D00149B	K02			D41211P	20			ALL
0221	24		PK		5-2	34-53-11	D00149B	A03			D41211P	21			ALL
0222	24		PK		5-2	34-53-11	D00149B	B03			D41211P	22			ALL
0223	24		PK		5-2	34-53-11	D00149B	C03			D41211P	23			ALL
0224	24		PK		5-2	34-53-11	D00149B	D03			D41211P	24			ALL
0225	24		PK		5-2	34-53-11	D00149B	E03			D41211P	25			ALL
0226	24		PK		1-9	34-53-11	D00149A	D05			TB1202Y	B001	1A		ALL
0227	24		PK		1-9	34-53-11	D00149A	C05			TB1202Y	B001	1A		ALL
0228	24		PK		1-8	34-53-11	D00149B	J05			TB1202Y	B001	1A		ALL
2001B	24		Y2	A	6-4	34-53-11	D41217P	14			D00149A	F07			ALL
2001R	24		Y2	A	0-0	34-53-11	D41217P	13			D00149A	E07			ALL
2001Z				A	0-0	34-53-11	D41217P	S/R			GB01202	ST..	1A		ALL
2004B	24		Y2	D	5-3	34-45-21	D00149A	F05			D41211P	30			ALL
2004R	24		Y2	D	0-0	34-45-21	D00149A	E05			D41211P	29			ALL
2004Z				D	0-0	34-45-21	GB01202	ST..	1A		D41211P	S/R			ALL
2005B	24		Y2	E	5-3	34-45-21	D00149A	H05			D41211P	34			YC051-YD157
2005B	24		Y2	E	2-1	34-45-21	D00149A	H05			TB1202Y	B017	1A		YD158-YR328
2005R	24		Y2	E	0-0	34-45-21	D00149A	G05			D41211P	33			YC051-YD157
2005R	24		Y2	E	0-0	34-45-21	D00149A	G05			TB1202Y	A017	1A		YD158-YR328
2005Z				E	0-0	34-45-21	GB01202	ST..	1A		D41211P	S/R			YC051-YD157
2005Z				E	0-0	34-45-21	D00149A	DED			GB01202	ST..	1A		YD158-YL999, YR301-YR328 YN231-YN501
2005Z				E	0-0	34-45-21	GB01202	ST..	1A		D00149A	DED			ALL
2006B	24		Y2	AA	1-8	34-55-11	D00161B	E03			TB1204Y	B001	1A		ALL
2006R	24		Y2	AA	0-0	34-55-11	D00161B	D03			TB1204Y	A001	1A		ALL
2006Z				AA	0-0	34-55-11	D00161B	DED			GB01204	ST..	1A		ALL
2007B	24		Y2	G	6-6	34-55-11	D04029P	25			TB1204Y	B001	1A		ALL
2007R	24		Y2	G	0-0	34-55-11	D04029P	24			TB1204Y	A001	1A		ALL
2007Z				G	0-0	34-55-11	D04029P	S/R			GB01204	ST..	1A		ALL
2008B	24		Y2	H	6-1	34-55-11	D00161B	H03			D41211P	36			ALL
2008R	24		Y2	H	0-0	34-55-11	D00161B	G03			D41211P	35			ALL
2008Z				H	0-0	34-55-11	GB01204	ST..	1A		D41211P	S/R			ALL
2009B	24		M5	J	6-2	34-55-11	D00161B	B01			D04269P	11			ALL
2009R	24		M5	J	0-0	34-55-11	D00161B	A01			D04269P	10			ALL
2009ZI				J	0-0	34-55-11	D00161B	DED			D04269P	12			ALL
2009ZO				J	0-0	34-55-11	GB01204	ST..	1A		D04269P	S/R			ALL
2011B	24		Y2	L	1-8	34-55-11	D00161B	H01			TB1204Y	B005	1A		ALL
2011R	24		Y2	L	0-0	34-55-11	D00161B	G01			TB1204Y	A005	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0120

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0121	286A0121				E1-2 SHELF (continued)										
2011Z				L	0-0	34-55-11	D00161B	DED			GB01204	ST..	1A		ALL
2012B	24		Y2	M	5-5	34-55-11	D45115P	32			TB1204Y	B005	1A		ALL
2012R	24		Y2	M	0-0	34-55-11	D45115P	31			TB1204Y	A005	1A		ALL
2012Z				M	0-0	34-55-11	D45115P	S/R			GB01204	ST..	1A		ALL
2013B	24		Y2	N	6-8	34-55-11	D41251P	12			TB1204Y	B005	1A		ALL
2013R	24		Y2	N	0-0	34-55-11	D41251P	11			TB1204Y	A005	1A		ALL
2013Z				N	0-0	34-55-11	D41251P	S/R			GB01204	ST..	1A		ALL
2014B	24		Y2	P	2-2	34-31-11	D10719B	H01			TB1201Z	B001	1A		ALL
2014R	24		Y2	P	0-0	34-31-11	D10719B	G01			TB1201Z	A001	1A		ALL
2014Z				P	0-0	34-31-11	D10719B	PERG	1A		GB01201	ST..	1A		ALL
2015B	24		Y2	Q	5-5	34-31-11	D04205P	11			TB1201Z	B001	1A		YC051-YD157
2015B	24		Y2	Q	5-5	34-31-11	D04205P	15			TB1201Z	B001	1A		YD158-YR328
2015R	24		Y2	Q	0-0	34-31-11	D04205P	10			TB1201Z	A001	1A		YC051-YD157
2015R	24		Y2	Q	0-0	34-31-11	D04205P	14			TB1201Z	A001	1A		YD158-YR328
2015Z				Q	0-0	34-31-11	D04205P	S/R			GB01201	ST..	1A		ALL
2016B	24		Y2	R	4-9	34-31-11	D45115P	14			TB1201Z	B001	1A		ALL
2016R	24		Y2	R	0-0	34-31-11	D45115P	13			TB1201Z	A001	1A		ALL
2016Z				R	0-0	34-31-11	D45115P	S/R			GB01201	ST..	1A		ALL
2017B	24		Y2	S	4-9	34-31-11	D45115P	16			TB1201Z	B001	1A		ALL
2017R	24		Y2	S	0-0	34-31-11	D45115P	15			TB1201Z	A001	1A		ALL
2017Z				S	0-0	34-31-11	D45115P	S/R			GB01201	ST..	1A		ALL
2018B	24		Y2	T	4-9	34-31-11	D45115P	18			TB1201Z	B001	1A		ALL
2018R	24		Y2	T	0-0	34-31-11	D45115P	17			TB1201Z	A001	1A		ALL
2018Z				T	0-0	34-31-11	D45115P	S/R			GB01201	ST..	1A		ALL
2020B	24		Y2	V	6-1	34-31-11	D41251P	4			TB1201Z	B001	1A		YC051-YD158
2020B	24		Y2	V	1-4	34-31-11	TB1201Y	B007	1A		TB1201Z	B001	1A		YL951-YR328
2020R	24		Y2	V	0-0	34-31-11	D41251P	3			TB1201Z	A001	1A		YC051-YD158
2020R	24		Y2	V	0-0	34-31-11	TB1201Y	A007	1A		TB1201Z	A001	1A		YL951-YR328
2020Z				V	0-0	34-31-11	D41251P	S/R			GB01201	ST..	1A		YC051-YD158
2020Z				V	0-0	34-31-11	GB01201	ST..	1A		GB01201	ST..	1A		YL951-YR328
2021B	24		Y2	X	6-1	34-31-11	D41251P	6			TB1201Z	B001	1A		ALL
2021R	24		Y2	X	0-0	34-31-11	D41251P	5			TB1201Z	A001	1A		ALL
2021Z				X	0-0	34-31-11	D41251P	S/R			GB01201	ST..	1A		ALL
2023B	24		Y2	W	5-5	34-51-11	D04029P	21			TB1201Y	B005	1A		ALL
2023R	24		Y2	W	0-0	34-51-11	D04029P	20			TB1201Y	A005	1A		ALL
2023Z				W	0-0	34-51-11	D04029P	S/R			GB01201	ST..	1A		ALL
2024B	24		Y2	AB	1-11	34-51-11	D03623B	C11			TB1201Y	B005	1A		ALL
2024R	24		Y2	AB	0-0	34-51-11	D03623B	B11			TB1201Y	A005	1A		ALL
2024Z				AB	0-0	34-51-11	D03623B	PERG	1A		GB01201	ST..	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0120

Page 5

Nov 12/2012

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0121	286A0121			E1-2 SHELF (continued)											
2025B	24	Y2	AC		2-2	34-51-11	D00161B	B03			TB1201Y	B005	1A		ALL
2025R	24	Y2	AC		0-0	34-51-11	D00161B	A03			TB1201Y	A005	1A		ALL
2025Z			AC		0-0	34-51-11	GB01204	ST..	1A		GB01201	ST..	1A		ALL
2026B	24	Y2	AD		2-0	34-51-11	D03623B	C13			TB1201Z	B009	1A		ALL
2026R	24	Y2	AD		0-0	34-51-11	D03623B	B13			TB1201Z	A009	1A		ALL
2026Z			AD		0-0	34-51-11	D03623B	PERG	1A		GB01201	ST..	1A		ALL
2027B	24	Y2	AE		6-1	34-51-11	D04205P	6			TB1201Z	B009	1A		ALL
2027R	24	Y2	AE		0-0	34-51-11	D04205P	5			TB1201Z	A009	1A		ALL
2027Z			AE		0-0	34-51-11	D04205P	S/R			GB01201	ST..	1A		ALL
2028B	24	Y2	AF		4-10	34-51-11	D45115P	24			TB1201Z	B009	1A		ALL
2028R	24	Y2	AF		0-0	34-51-11	D45115P	23			TB1201Z	A009	1A		ALL
2028Z			AF		0-0	34-51-11	D45115P	S/R			GB01201	ST..	1A		ALL
2029B	24	Y2	AG		4-10	34-51-11	D45115P	26			TB1201Z	B009	1A		ALL
2029R	24	Y2	AG		0-0	34-51-11	D45115P	25			TB1201Z	A009	1A		ALL
2029Z			AG		0-0	34-51-11	D45115P	S/R			GB01201	ST..	1A		ALL
2030B	24	Y2	AH		4-10	34-51-11	D45115P	28			TB1201Z	B009	1A		ALL
2030R	24	Y2	AH		0-0	34-51-11	D45115P	27			TB1201Z	A009	1A		ALL
2030Z			AH		0-0	34-51-11	D45115P	S/R			GB01201	ST..	1A		ALL
2031B	24	Y2	AJ		6-2	34-51-11	D41251P	8			TB1201Z	B009	1A		ALL
2031R	24	Y2	AJ		0-0	34-51-11	D41251P	7			TB1201Z	A009	1A		ALL
2031Z			AJ		0-0	34-51-11	D41251P	S/R			GB01201	ST..	1A		ALL
2032B	24	Y2	AK		6-2	34-51-11	D41251P	10			TB1201Z	B009	1A		ALL
2032R	24	Y2	AK		0-0	34-51-11	D41251P	9			TB1201Z	A009	1A		ALL
2032Z			AK		0-0	34-51-11	D41251P	S/R			GB01201	ST..	1A		ALL
2033B	24	Y2	AL		4-10	34-51-11	D03623B	B04			D45115P	22			ALL
2033R	24	Y2	AL		0-0	34-51-11	D03623B	A04			D45115P	21			ALL
2033Z			AL		0-0	34-51-11	D03623B	PERG	1A		D45115P	S/R			ALL
2034B	24	Y2	AM		5-5	34-55-11	D45115P	34			TB1204Y	B005	1A		ALL
2034R	24	Y2	AM		0-0	34-55-11	D45115P	33			TB1204Y	A005	1A		ALL
2034Z			AM		0-0	34-55-11	D45115P	S/R			GB01204	ST..	1A		ALL
2035B	24	Y2	AN		6-7	34-21-14	D00149A	J07			D41251P	16			ALL
2035R	24	Y2	AN		0-0	34-21-14	D00149A	H07			D41251P	15			ALL
2035Z			AN		0-0	34-21-14	GB01202	ST..	1A		D41251P	S/R			ALL
2036B	24	Y2	AP		2-4	34-31-11	D10719B	B01			TB1201Y	B013	1A		ALL
2036R	24	Y2	AP		0-0	34-31-11	D10719B	A01			TB1201Y	A013	1A		ALL
2036Z			AP		0-0	34-31-11	D10719B	PERG	1A		GB01201	ST..	1A		ALL
2037B	24	Y2	AQ		5-0	34-31-11	D45115P	12			TB1201Y	B013	1A		ALL
2037R	24	Y2	AQ		0-0	34-31-11	D45115P	11			TB1201Y	A013	1A		ALL
2037Z			AQ		0-0	34-31-11	D45115P	S/R			GB01201	ST..	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0120

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0121	286A0121				E1-2 SHELF (continued)										
2038B	24	Y2	AR		4-8	34-31-11	D41127P	7			TB1201Y	B013	1A		ALL
2038R	24	Y2	AR		0-0	34-31-11	D41127P	6			TB1201Y	A013	1A		ALL
2038Z			AR		0-0	34-31-11	D41127P	S/R			GB01201	ST..	1A		ALL
2039B	24	Y2	AS		5-3	34-31-11	D10719B	K01			D04029P	29			YC051-YC058
2039B	24	Y2	AS		5-2	34-31-11	D10719B	K01			D04029P	29			YC059-YR328
2039R	24	Y2	AS		0-0	34-31-11	D10719B	J01			D04029P	28			ALL
2039Z			AS		0-0	34-31-11	D10719B	PERG	1A		D04029P	S/R			ALL
2040B	24	Y2	AT		2-11	34-21-13	D41251P	14			D04205P	2			ALL
2040R	24	Y2	AT		0-0	34-21-13	D41251P	13			D04205P	1			ALL
2040Z			AT		0-0	34-21-13	D41251P	S/R			D04205P	S/R			ALL
2041B	24	Y2	AU		3-4	34-57-11	D04205P	4			D45115P	36			ALL
2041R	24	Y2	AU		0-0	34-57-11	D04205P	3			D45115P	35			ALL
2041Z			AU		0-0	34-57-11	D04205P	S/R			D45115P	S/R			ALL
2044B	24	Y2	AX		4-10	34-21-24	D00149B	B05			D41213P	17			ALL
2044R	24	Y2	AX		0-0	34-21-24	D00149B	A05			D41213P	16			ALL
2044Z			AX		0-0	34-21-24	GB01202	ST..	1A		D41213P	S/R			ALL
2045B	24	Y2	Z		6-8	34-61-14	D41251P	2			TB1204Y	B001	1A		ALL
2045R	24	Y2	Z		0-0	34-61-14	D41251P	1			TB1204Y	A001	1A		ALL
2045Z			Z		0-0	34-61-14	D41251P	S/R			GB01204	ST..	1A		ALL
2046B	24	Y2	AZ		3-4	22-11-51	D04029P	18			D45115P	52			ALL
2046R	24	Y2	AZ		0-0	22-11-51	D04029P	17			D45115P	51			ALL
2046Z			AZ		0-0	22-11-51	D04029P	S/R			D45115P	S/R			ALL
2052B	24	Y2	BU		2-4	31-62-15	D45115P	30			D41127P	5			ALL
2052R	24	Y2	BU		0-0	31-62-15	D45115P	29			D41127P	4			ALL
2052Z			BU		0-0	31-62-15	D45115P	S/R			D41127P	S/R			ALL
2053B	24	Y2	AI		4-11	23-27-37	D41213P	2			D00149A	REF	VP		YD158-YD170, YN231-YN260
2053B	24	Y2	DA		4-11	23-27-37	D00149A	REF	VP		D41213P	2			YL951-YL999
2053R	24	Y2	AI		0-0	23-27-37	D41213P	1			D00149A	REF	VP		YD158-YD170, YN231-YN260
2053R	24	Y2	DA		0-0	23-27-37	D00149A	REF	VP		D41213P	1			YL951-YL999
2053Z			AI		0-0	23-27-37	D41213P	S/R			D00149A	DED			YD158-YD170, YN231-YN260
2053Z			DA		0-0	23-27-37	D00149A	DED			D41213P	S/R			YL951-YL999
2055B	24	Y2	BM		5-4	34-58-11	D10719B	D02			D41251P	26			ALL
2055R	24	Y2	BM		0-0	34-58-11	D10719B	C02			D41251P	25			ALL
2055Z			BM		0-0	34-58-11	D10719B	PERG	1A		D41251P	S/R			ALL
2056B	24	Y2	BN		5-4	34-58-11	D10719B	B08			D41251P	28			ALL
2056R	24	Y2	BN		0-0	34-58-11	D10719B	A08			D41251P	27			ALL

WIRE LIST

D280A108

91-21-11

Section W0120

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To							
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice
W0121	286A0121			E1-2 SHELF (continued)											
2056Z				BN	0-0	34-58-11	D10719B	PERG	1A		D41251P	S/R			ALL
2057B	24		Y2	BP	5-4	34-58-11	D10719B	K02			D41251P	30			ALL
2057R	24		Y2	BP	0-0	34-58-11	D10719B	J02			D41251P	29			ALL
2057Z				BP	0-0	34-58-11	D10719B	PERG	1A		D41251P	S/R			ALL
2058B	24		Y2	BQ	5-4	34-58-11	D10719B	H08			D41251P	32			YC051-YD158
2058R	24		Y2	BQ	0-0	34-58-11	D10719B	G08			D41251P	31			YC051-YD158
2058Z				BQ	0-0	34-58-11	D10719B	PERG	1A		D41251P	S/R			YC051-YD158
2059B	24		Y2	BT	2-5	34-58-11	D10719B	F09			TB1201Y	B019	1A		YC053-YR328
2059R	24		Y2	BT	0-0	34-58-11	D10719B	E09			TB1201Y	A019	1A		YC053-YR328
2059Z				BT	0-0	34-58-11	D10719B	PERG	1A		GB01201	ST..	1A		YC053-YR328
2062B	24		Y2	DE	5-3	34-45-21	TB1202Y	B017	1A		D41211P	34			YD158-YD170, YN231-YN260
2062B	24		Y2	HD	5-3	34-45-21	TB1202Y	B017	1A		D41211P	34			YL951-YL999, YN501-YR328
2062R	24		Y2	DE	0-0	34-45-21	TB1202Y	A017	1A		D41211P	33			YD158-YD170, YN231-YN260
2062R	24		Y2	HD	0-0	34-45-21	TB1202Y	A017	1A		D41211P	33			YL951-YL999, YN501-YR328
2062Z				DE	0-0	34-45-21	GB01202	ST..	1A		D41211P	S/R			YD158-YD170, YN231-YN260
2062Z				HD	0-0	34-45-21	GB01202	ST..	1A		D41211P	S/R			YL951-YL999, YN501-YR328
2064B	24		Y2	DG	5-3	34-45-21	TB1202Y	B017	1A		D45115P	48			YD158-YN260, YR301-YR328
2064B	24		Y2	HF	5-3	34-45-21	TB1202Y	B017	1A		D45115P	48			YN501
2064R	24		Y2	DG	0-0	34-45-21	TB1202Y	A017	1A		D45115P	47			YD158-YN260, YR301-YR328
2064R	24		Y2	HF	0-0	34-45-21	TB1202Y	A017	1A		D45115P	47			YN501
2064Z				DG	0-0	34-45-21	GB01202	ST..	1A		D45115P	S/R			YD158-YN260, YR301-YR328
2064Z				HF	0-0	34-45-21	GB01202	ST..	1A		D45115P	S/R			YN501
2065B	24		Y2	CA	5-0	34-58-11	D41211P	38			TB1201Y	B019	1A		YC053-YD170
2065B	24		Y2	CA	5-0	34-58-11	TB1201Y	B019	1A		D41211P	38			YL951-YR328
2065R	24		Y2	CA	0-0	34-58-11	D41211P	37			TB1201Y	A019	1A		YC053-YD170
2065R	24		Y2	CA	0-0	34-58-11	TB1201Y	A019	1A		D41211P	37			YL951-YR328
2065Z				CA	0-0	34-58-11	D41211P	S/R			GB01201	ST..	1A		YC053-YD170
2065Z				CA	0-0	34-58-11	GB01201	ST..	1A		D41211P	S/R			YL951-YR328
2066B	24		Y2	CB	5-1	34-58-11	D45115P	38			TB1201Y	B019	1A		YC053-YD170
2066B	24		Y2	CB	5-1	34-58-11	TB1201Y	B019	1A		D45115P	38			YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0120

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0121	286A0121				E1-2 SHELF (continued)										
2066R	24	Y2	CB		0-0	34-58-11	D45115P	37			TB1201Y	A019	1A		YC053-YD170
2066R	24	Y2	CB		0-0	34-58-11	TB1201Y	A019	1A		D45115P	37			YL951-YR328
2066Z			CB		0-0	34-58-11	D45115P	S/R			GB01201	ST..	1A		YC053-YD170
2066Z			CB		0-0	34-58-11	GB01201	ST..	1A		D45115P	S/R			YL951-YR328
2079B	24	Y2	CZ		3-6	22-11-53	D41251P	20			D45115P	20			YC059-YR328
2079R	24	Y2	CZ		0-0	22-11-53	D41251P	19			D45115P	19			YC059-YR328
2079Z			CZ		0-0	22-11-53	D41251P	S/R			D45115P	S/R			YC059-YR328
2085B	24	Y2	EI		6-1	34-31-11	D41251P	39			TB1201Y	B007	1A		YL951-YR328
2085R	24	Y2	EI		0-0	34-31-11	D41251P	38			TB1201Y	A007	1A		YL951-YR328
2085Z			EI		0-0	34-31-11	D41251P	S/R			GB01201	ST..	1A		YL951-YR328
2086B	24	Y2	EJ		6-1	34-31-11	D41251P	4			TB1201Y	B007	1A		YL951-YR328
2086R	24	Y2	EJ		0-0	34-31-11	D41251P	3			TB1201Y	A007	1A		YL951-YR328
2086Z			EJ		0-0	34-31-11	D41251P	S/R			GB01201	ST..	1A		YL951-YR328
2502B	24	Y2	DD		2-11	34-21-13	D04205P	9			D41251P	49			YC051-YD170
2502B	24	Y2	AY		2-11	34-21-13	D04205P	9			D41251P	49			YL951-YL999, YR301-YR328
2502B	24	Y2	BI		2-11	34-21-13	D04205P	9			D41251P	49			YN231-YN501
2502R	24	Y2	DD		0-0	34-21-13	D04205P	8			D41251P	48			YC051-YD170
2502R	24	Y2	AY		0-0	34-21-13	D04205P	8			D41251P	48			YL951-YL999, YR301-YR328
2502R	24	Y2	BI		0-0	34-21-13	D04205P	8			D41251P	48			YN231-YN501
2502Z			DD		0-0	34-21-13	D04205P	S/R			D41251P	S/R			YC051-YD170
2502Z			AY		0-0	34-21-13	D04205P	S/R			D41251P	S/R			YL951-YL999, YR301-YR328
2502Z			BI		0-0	34-21-13	D04205P	S/R			D41251P	S/R			YN231-YN501
2503B	24	Y2	AI		1-10	31-62-11	D04205P	15			D45201P	30			YC051-YD157
2503R	24	Y2	AI		0-0	31-62-11	D04205P	14			D45201P	29			YC051-YD157
2503Z			AI		0-0	31-62-11	D04205P	S/R			D45201P	S/R			YC051-YD157
2504B	24	M5	CD		4-7	34-31-11	D10719B	K10			D04269P	2			ALL
2504R	24	M5	CD		0-0	34-31-11	D10719B	J10			D04269P	1			ALL
2504ZI			CD		0-0	34-31-11	D10719B	DED			D04269P	3			ALL
2504ZO			CD		0-0	34-31-11	D10719B	PERG	1A		D04269P	S/R			ALL
2505B	24	M5	CE		4-10	34-32-11	D03623B	D04			D04269P	5			ALL
2505R	24	M5	CE		0-0	34-32-11	D03623B	C04			D04269P	4			ALL
2505ZI			CE		0-0	34-32-11	D03623B	DED			D04269P	6			ALL
2505ZO			CE		0-0	34-32-11	D03623B	PERG	1A		D04269P	S/R			ALL
2506B	24	M5	CF		4-10	34-51-11	D03623B	C07			D04269P	8			ALL
2506R	24	M5	CF		0-0	34-51-11	D03623B	B07			D04269P	7			ALL
2506ZI			CF		0-0	34-51-11	D03623B	DED			D04269P	9			ALL

WIRE LIST

D280A108

91-21-11

Section W0120

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W0121	286A0121	E1-2 SHELF (continued)													
2506ZO		CF	0-0	34-51-11	D03623B	PERG	1A		D04269P	S/R				ALL	
2510B	24	Y2	DH	5-3	22-11-51	D41211P		48	D00149A	B07				YD158-YR328	
2510R	24	Y2	DH	0-0	22-11-51	D41211P		47	D00149A	A07				YD158-YR328	
2510Z		DH	0-0	22-11-51	D41211P	S/R			GB01202	ST..	1A			YD158-YR328	
2511B	24	Y2	DI	6-7	34-21-13	D41251P		51	D00149A	D02				YD158-YR328	
2511R	24	Y2	DI	0-0	34-21-13	D41251P		50	D00149A	C02				YD158-YR328	
2511Z		DI	0-0	34-21-13	D41251P	S/R			GB01202	ST..	1A			YD158-YR328	
2514B	24	Y2	DL	2-2	34-61-14	D00149A		B06	TB1204Y	B001	1A			YD158-YR328	
2514R	24	Y2	DL	0-0	34-61-14	D00149A		A06	TB1204Y	A001	1A			YD158-YR328	
2514Z		DL	0-0	34-61-14	GB01204	ST..	1A		GB01202	ST..	1A			YD158-YR328	
2515B	22	X2	DM	2-1	34-53-11	TB1201Y		B019	D00149A	B02				YD158-YR328	
2515R	22	X2	DM	0-0	34-53-11	TB1201Y		A019	D00149A	A02				YD158-YR328	
2515Z		DM	0-0	34-53-11	GB01201	ST..	1A		GB01202	ST..	1A			YD158-YR328	
2516B	24	Y2	YZ	6-8	31-31-13	D45002P		2	D00149A	F02				YL963-YL999, YN236-YR328	
2516R	24	Y2	YZ	0-0	31-31-13	D45002P		1	D00149A	E02				YL963-YL999, YN236-YR328	
2516Z		YZ	0-0	31-31-13	D45002P	S/R			GB01202	ST..	1A			YL963-YL999, YN236-YR328	
W0122	286A0122	J11 RELAY PANEL - LANDING GEAR HYDRAULICS (WITH E-6)													
0001	18	PA	1-10	29-25-11	D46618J			1	TB0025Y	A001	1D			YC051-YC053	
0001	18	PA	1-5	29-25-11	D46618J			1	TB0025Y	A001	1D			YC054-YC057, YC059-YR328	
0001	18	PA	1-3	29-25-11	D46618J			1	TB0025Y	A001	1D			YC058	
0002	18	PA	1-10	29-25-11	D46618J			2	TB0025Y	A003	1D			YC051-YC053	
0002	18	PA	1-5	29-25-11	D46618J			2	TB0025Y	A003	1D			YC054-YC057, YC059-YR328	
0002	18	PA	1-3	29-25-11	D46618J			2	TB0025Y	A003	1D			YC058	
0003	18	PA	1-10	29-25-11	D46618J			3	TB0025Y	A005	1D			YC051-YC053	
0003	18	PA	1-4	29-25-11	D46618J			3	TB0025Y	A005	1D			YC054-YC057, YL963-YL999, YN236-YR328	
0003	18	PA	1-3	29-25-11	D46618J			3	TB0025Y	A005	1D			YC058	
0003	18	PA	1-5	29-25-11	D46618J			3	TB0025Y	A005	1D			YC059-YL959, YN231-YN235	
0004	20	PA	1-8	29-25-11	D46618J			4	D11370	X1				YC051-YC053	
0004	20	PA	1-7	29-25-11	D46618J			4	D11370	X1				YC054-YC057, YC059-YR328	

WIRE LIST

D280A108

91-21-11

Section W0120

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0122	286A0122			J11 RELAY PANEL - LANDING GEAR HYDRAULICS (WITH E-6) (continued)											
0004	20	PA			1-6	29-25-11	D46618J		4		D11370	X1			YC058
0005	22	PA			1-10	29-25-11	D46618J		5		TB0025V	A009	1		YC051-YC053
0005	22	PA			1-5	29-25-11	D46618J		5		TB0025V	A009	1		YC054-YC057, YC059-YR328
0005	22	PA			1-4	29-25-11	D46618J		5		TB0025V	A009	1		YC058
0006	18	PA			1-10	29-25-11	D46618J		6		TB0025V	A011	1		YC051-YC053
0006	18	PA			1-5	29-25-11	D46618J		6		TB0025V	A011	1		YC054-YC057, YC059-YR328
0006	18	PA			1-4	29-25-11	D46618J		6		TB0025V	A011	1		YC058
0007	18	PA			1-8	29-25-11	D46618J		7		D11370	A2			YC051-YC053
0007	18	PA			1-7	29-25-11	D46618J		7		D11370	A2			YC054-YC057, YC059-YR328
0007	18	PA			1-6	29-25-11	D46618J		7		D11370	A2			YC058
0008	18	PA			1-10	29-25-11	D46618J		8		TB0025V	B011	1		YC051-YC053
0008	18	PA			1-5	29-25-11	D46618J		8		TB0025V	B011	1		YC054-YC057, YC059-YR328
0008	18	PA			1-4	29-25-11	D46618J		8		TB0025V	B011	1		YC058
0009	18	PA			1-8	29-25-11	D46618J		9		D03254	B2			YC051-YC053, YC059-YR328
0009	18	PA			1-7	29-25-11	D46618J		9		D03254	B2			YC054-YC058
0010	22	PA			1-8	29-25-11	D46618J		10		D03254	A2			YC051-YC053, YC059-YR328
0010	22	PA			1-7	29-25-11	D46618J		10		D03254	A2			YC054-YC058
0011	22	PA			1-8	29-25-11	D46618J		11		D11370	X2			YC051-YC053
0011	22	PA			1-7	29-25-11	D46618J		11		D11370	X2			YC054-YC057, YC059-YR328
0011	22	PA			1-6	29-25-11	D46618J		11		D11370	X2			YC058
0012	18	PA			1-7	29-25-11	TB0025Y	B001	1D		TB0025V	A011	1		YC051-YC053
0012	18	PA			1-4	29-25-11	TB0025Y	B001	1D		TB0025V	A011	1		YC054-YC057, YL963-YL999, YN236-YR328
0012	18	PA			1-3	29-25-11	TB0025Y	B001	1D		TB0025V	A011	1		YC058-YL959, YN231-YN235
0013	18	PA			1-7	29-25-11	TB0025Y	B003	1D		TB0025V	B011	1		YC051-YC053
0013	18	PA			1-4	29-25-11	TB0025Y	B003	1D		TB0025V	B011	1		YC054-YC057, YL963-YL999, YN236-YR328
0013	18	PA			1-3	29-25-11	TB0025Y	B003	1D		TB0025V	B011	1		YC058-YL959, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W0120

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0122	286A0122			J11 RELAY PANEL - LANDING GEAR HYDRAULICS (WITH E-6) (continued)											
0014	18	PA			1-7	29-25-11	TB0025Y	B005	1D		TB0025V	A011	1		YC051-YC053
0014	18	PA			1-4	29-25-11	TB0025Y	B005	1D		TB0025V	A011	1		YC054-YC058, YL963-YL999, YN236-YR328
0014	18	PA			1-2	29-25-11	TB0025Y	B005	1D		TB0025V	A011	1		YC059-YL959, YN231-YN235
0015	18	PA			1-8	29-25-11	D03254	B1			TB0025V	B009	1		YC051-YC053
0015	18	PA			1-7	29-25-11	D03254	B1			TB0025V	B009	1		YC054-YC058
0015	18	PA			1-5	29-25-11	D03254	B1			TB0025V	B009	1		YC059-YR328
0016	22	PA			1-8	29-25-11	D03254	A1			TB0025V	A009	1		YC051-YC053
0016	22	PA			1-7	29-25-11	D03254	A1			TB0025V	A009	1		YC054-YC058
0016	22	PA			1-5	29-25-11	D03254	A1			TB0025V	A009	1		YC059-YR328
0017	22	PA			1-8	29-25-11	D03254	X2			TB0025V	A009	1		YC051-YC053
0017	22	PA			1-7	29-25-11	D03254	X2			TB0025V	A009	1		YC054-YC058
0017	22	PA			1-5	29-25-11	D03254	X2			TB0025V	A009	1		YC059-YR328
0018	20	PA			1-8	29-25-11	D03254	X1			TB0025V	B009	1		YC051-YC053
0018	20	PA			1-7	29-25-11	D03254	X1			TB0025V	B009	1		YC054-YC058
0018	20	PA			1-5	29-25-11	D03254	X1			TB0025V	B009	1		YC059-YR328
0019	18	PA			1-8	29-25-11	D11370	A3			TB0025V	B009	1		YC051-YC053
0019	18	PA			1-7	29-25-11	D11370	A3			TB0025V	B009	1		YC054-YC058
0019	18	PA			1-5	29-25-11	D11370	A3			TB0025V	B009	1		YC059-YR328
0020	18	PA			1-8	29-25-11	D11370	A1			TB0025V	B011	1		YC051-YC053
0020	18	PA			1-7	29-25-11	D11370	A1			TB0025V	B011	1		YC054-YC058
0020	18	PA			1-5	29-25-11	D11370	A1			TB0025V	B011	1		YC059-YR328
0021	18	HL			1-0	27-31-11	D46618J		16		D12968	A2			YC051-YC053
0022	18	HL			1-0	27-31-11	SM00096		9		D12968	A1			YC051-YC053
0022	20	PA			1-4	27-31-11	SM00096		9		D12968	A1			YC054-YC057
0022	20	PA			1-6	27-31-11	TB0025Y	A013	1A		D12968	A1			YC058-YL959, YN231-YN235
0022	20	PA			1-4	27-31-11	TB0025Y	A013	1A		D12968	A1			YL963-YL999, YN236-YR328
0023	18	HL			1-0	27-31-11	SM00096		9		D12968	X1			YC051-YC053
0023	20	PA			1-4	27-31-11	SM00096		9		D12968	X1			YC054-YC057
0023	20	PA			1-6	27-31-11	TB0025Y	A013	1A		D12968	X1			YC058-YL959, YN231-YN235
0023	20	PA			1-4	27-31-11	TB0025Y	A013	1A		D12968	X1			YL963-YL999, YN236-YR328
0024	18	HL			1-0	27-31-11	D46618J		14		D12968	X2			YC051-YC053
0025	18	HL			0-7	27-31-11	D46618J		15		SM00096		9		YC051-YC053

WIRE LIST

D280A108

91-21-11

Section W0120

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0122	286A0122			J11 RELAY PANEL - LANDING GEAR HYDRAULICS (WITH E-6) (continued)											
0026	20	PA			1-2	27-31-11	D46616J		1		SM00096		9		YC054-YC057
0026	20	PA			1-7	27-31-11	D46616J		1		TB0025Y	A013	1A		YC058-YL959, YN231-YN235
0026	20	PA			1-5	27-31-11	D46616J		1		TB0025Y	A013	1A		YL963-YL999, YN236-YR328
0027	20	PA			1-4	27-31-11	D46616J		2		D12968	A2			YC054-YC057
0027	20	PA			1-3	27-31-11	D46616J		2		D12968	A2			YC058, YL963-YL999, YN236-YR328
0027	20	PA			1-5	27-31-11	D46616J		2		D12968	A2			YC059-YL959, YN231-YN235
0028	20	PA			1-4	27-31-11	D46616J		3		D12968	X2			YC054-YC057
0028	20	PA			1-3	27-31-11	D46616J		3		D12968	X2			YC058, YL963-YL999, YN236-YR328
0028	20	PA			1-5	27-31-11	D46616J		3		D12968	X2			YC059-YL959, YN231-YN235
0029	20	PA			2-0	27-31-37	D11179		2		D46616J	5			YC051-YC057
0029	24	PK			1-3	27-31-37	D46616J		5		D11179	2			YC058
0029	24	PK			1-4	27-31-37	D46616J		5		D11179	2			YC059-YL959, YN231-YN235
0029	24	PK			1-2	27-31-37	D46616J		5		D11179	2			YL963-YL999, YN236-YR328
0030	20	PA			2-0	27-31-37	D11179		3		D46616J	6			YC051-YC057
0030	20	PA			1-3	27-31-37	D46616J		6		D11179	3			YC058
0030	20	PA			1-4	27-31-37	D46616J		6		D11179	3			YC059-YL959, YN231-YN235
0030	20	PA			1-2	27-31-37	D46616J		6		D11179	3			YL963-YL999, YN236-YR328
0031	20	PA			2-0	27-31-37	D11179		5		D46616J	7			YC051-YC057
0031	24	PK			1-3	27-31-37	D46616J		7		D11179	5			YC058
0031	24	PK			1-4	27-31-37	D46616J		7		D11179	5			YC059-YL959, YN231-YN235
0031	24	PK			1-2	27-31-37	D46616J		7		D11179	5			YL963-YL999, YN236-YR328
0032	20	PA			2-0	27-31-37	D11179		7		D46616J	4			YC051-YC057
0032	20	PA			1-3	27-31-37	D46616J		4		D11179	7			YC058
0032	20	PA			1-4	27-31-37	D46616J		4		D11179	7			YC059-YL959, YN231-YN235
0032	20	PA			1-2	27-31-37	D46616J		4		D11179	7			YL963-YL999, YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W0120

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0122	286A0122			J11 RELAY PANEL - LANDING GEAR HYDRAULICS (WITH E-6) (continued)											
0033	20		PA		1-4	27-41-12	D46616J		25		D13364		B2		YC059-YL959, YN231-YN235
0033	20		PA		1-3	27-41-12	D46616J		25		D13364		B2		YL963-YL999, YN236-YR328
0034	20		PA		1-4	27-41-12	D46616J		21		D13364		D2		YC059-YL959, YN231-YN235
0034	20		PA		1-3	27-41-12	D46616J		21		D13364		D2		YL963-YL999, YN236-YR328
0035	18		PA		1-4	27-41-12	D46616J		20		D13364		A2		YC059-YL959, YN231-YN235
0035	18		PA		1-3	27-41-12	D46616J		20		D13364		A2		YL963-YL999, YN236-YR328
0036	18		PA		1-4	27-41-12	D46616J		22		D13364		A1		YC059-YL959, YN231-YN235
0036	18		PA		1-3	27-41-12	D46616J		22		D13364		A1		YL963-YL999, YN236-YR328
0037	20		PA		1-4	27-41-12	D46616J		24		D13364		D1		YC059-YL959, YN231-YN235
0037	20		PA		1-3	27-41-12	D46616J		24		D13364		D1		YL963-YL999, YN236-YR328
0038	20		PA		1-4	27-41-12	D46616J		23		D13364		B1		YC059-YL959, YN231-YN235
0038	20		PA		1-3	27-41-12	D46616J		23		D13364		B1		YL963-YL999, YN236-YR328
0039	20		PA		1-4	27-41-12	D46616J		19		D13364		C1		YC059-YL959, YN231-YN235
0039	20		PA		1-3	27-41-12	D46616J		19		D13364		C1		YL963-YL999, YN236-YR328
0040	20		PA		1-4	27-41-12	D46616J		18		D13364		C2		YC059-YL959, YN231-YN235
0040	20		PA		1-3	27-41-12	D46616J		18		D13364		C2		YL963-YL999, YN236-YR328
0041	20		PA		1-4	27-41-12	D46616J		17		D13364		X1		YC059-YL959, YN231-YN235
0041	20		PA		1-3	27-41-12	D46616J		17		D13364		X1		YL963-YL999, YN236-YR328
0042	20		PA		1-4	27-41-12	D46616J		13		D13364		X2		YC059-YL959, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W0120

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0122	286A0122			J11 RELAY PANEL - LANDING GEAR HYDRAULICS (WITH E-6) (continued)											
0042	20		PA		1-3	27-41-12	D46616J		13		D13364		X2		YL963-YL999, YN236-YR328
0057	20		PA		1-3	33-26-31	D15706		A1		D46616J		8		YR315-YR328
0058	20		PA		1-3	33-26-31	D15706		A2		D46616J		9		YR315-YR328
0059	20		PA		1-3	33-26-31	D15706		X1		D46616J		10		YR315-YR328
0060	20		PA		1-3	33-26-31	D15706		X2		D46616J		11		YR315-YR328
0122	24		PK		1-7	23-71-01	D13187		5		D46623J		5		YL963-YL999, YN236-YR328
0123	24		PK		1-7	23-71-01	D13187		2		D46623J		2		YL963-YL999, YN236-YR328
0124	22		PA		1-7	23-71-01	D13187		7		D46623J		7		YL963-YL999, YN236-YR328
0125	22		PA		1-7	23-71-01	D13187		3		D46623J		3		YL963-YL999, YN236-YR328

WIRE LIST
D280A108

91-21-11
Section W0120
Page 15 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0130	286A0130				EMERGENCY AISLE LIGHTS										
0001	20		PA		7-7	33-51-12	D11344		1		L01065	=P	C		YC051-YN260
0002	20		PA		7-7	33-51-12	D11344		2		L01065	=G	C		YC051-YN260
W0131	286A0131				E001-03 SHELF										
0001	22		PA		1-11	32-42-11	D01040A		C02		GD01304	DC..	1A		ALL
0002	22		PA		1-10	32-42-11	D01040B		C15		GD01304	DC..	1A		ALL
0003	22		PA		1-11	32-41-11	GD01304		ST..	1A	D01040A	C13			ALL
0004	24		PK		1-9	31-31-15	D40488J		5		D43040J	23			ALL
0008	22		PA		1-8	23-31-02	TB1302Z		B017	1A	GD01302	ST..	1A		YC051-YR313
0009	24		PK		2-4	23-31-02	TB1302Z		A009	1A	D04195J	4			ALL
0010	20		GA		2-6	23-31-01	D46051J		4		TB1302Z	A009	1A		YC051-YC052
0010	20		PA		2-6	23-31-01	D46051J		4		TB1302Z	A009	1A		YC053-YC059
0010	20		PA		2-6	23-31-01	D46051J		3		TB1302Z	A009	1A		YC060-YR328
0011	20		PA		2-11	23-31-01	D41337J		9		TB1302Z	A009	1A		YC051-YN260
0011	20		PA		2-4	23-31-01	D41337J		9		TB1302Z	A009	1A		YN501-YR328
0012	20		PA		3-2	23-31-01	D04181J		10		TB1302Z	A009	1A		ALL
0013	20		GA		1-7	23-31-01	TB1302Z		A009	1A	D02639C	2			YC051-YC052
0013	20		PA		1-7	23-31-01	TB1302Z		A009	1A	D02639C	2			YC053-YC059
0013	18		PA		2-4	23-31-01	D46051J		4		D02639C	2			YC060-YR328
0014	24		PK		3-0	23-31-01	D04149J		1		TB1302Z	B009	1A		ALL
0015	24		PK		1-9	23-31-01	TB1302Z		B009	1A	D02639B	C01			ALL
0016	20		GA		1-5	23-31-01	GD01302		DC..	1A	D02639C	4			YC051-YC052
0016	20		PA		1-5	23-31-01	GD01302		DC..	1A	D02639C	4			YC053-YC059
0016	18		PA		1-7	23-31-01	GD01301		DC..	1	D02639C	4			YC060-YR328
0017	24		PK		0-7	23-31-02	D02639B		A10		D02639B	B10			ALL
0019	22		PA		2-4	23-31-02	D02639B		C09		D04195J	3			ALL
001CO				JA	0-0	23-12-11	D00199C		=C1		D04133J	=C1			ALL
001CX			OF	JA	1-10	23-12-11	D00199C		1	DN	D04133J	=A1			ALL
0020	24		PK		2-4	23-31-04	TB1302Z		B009	1A	D04195J	15			ALL
0021	24		PK		1-10	23-31-01	D02639B		C02		TB1302Z	A013	1A		ALL
0022	24		PK		2-5	23-31-04	TB1302Z		A013	1A	D04195J	18			ALL
0023	24		PK		2-8	23-31-04	D04195J		20		D04181J	6			YC051-YD170, YN231-YN501
0023	24		PK		2-3	23-31-04	D04195J		20		TB1302Y	B007	1A		YL951-YL999, YR301-YR328
0024	24		PK		2-5	23-31-04	D41337J		12		D04195J	19			YC051-YN260
0024	24		PK		1-10	23-31-04	D41337J		12		D04195J	19			YN501-YR328
0025	22		PA		2-3	SPARE	TB1304Y		CAP	Y	D41337J	2			YC051-YC052
0025	22		PA		3-0	23-31-06	TB1302Z		A013	1A	D41337J	2			YD158-YN260

WIRE LIST

D280A108

91-21-11

Section W0130

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0131	286A0131			E001-03 SHELF (continued)											
0026	22		PA		2-4	23-31-06	TB1304Z	A009	1A		D41337J	1			YC051-YD157
0026	22		PA		2-11	23-31-06	TB1302Z	B009	1A		D41337J	1			YD158-YN260
0027	22		PA		2-11	23-31-06	D02639B	D05			D41337J	3			YC051-YN260
0028	22		PA		2-5	23-31-06	TB1304Z	B013	1A		D41337J	6			YC051-YD170
0028	22		PA		2-5	23-31-06	D41337J	6			TB1304Z	B013	1A		YL951-YN260
0029	16		PA		2-2	23-12-11	D41831J	4			TB1301W	A001	1		YC051-YD157
0029	16		PA		2-3	23-12-11	D41831J	4			D00199C	2			YD158-YD170
0029	16		CQ		2-3	23-12-11	D41831J	4			D00199C	2			YL951-YR328
0030	16		PA		2-2	23-12-11	D41831J	7			TB1301W	A001	1		YC051-YD157
0030	22		PA		2-4	44-21-22	D02639B	D05			D41337J	3			YN501-YR328
0031	16		PA		1-5	23-12-11	TB1301W	A001	1		D00199C	2			YC051-YD157
0032	18		PA		2-9	23-12-11	D04123J	7			TB1301W	A001	1		YC051-YD157
0033	16		PA		1-4	23-12-11	GD01301	DC..	1		D00199C	4			YC051-YL999
0033	16		CQ		1-4	23-12-11	GD01301	DC..	1		D00199C	4			YN231-YR328
0034	22		PA		1-10	23-12-11	GD01302	DC..	1A		D00199B	D03			ALL
0035	22		PA		2-8	23-12-11	D04195J	34			D00199B	C01			ALL
0036	24		PK		2-5	23-12-11	D04195J	40			TB1301Y	A005	1A		ALL
0037	24		PK		2-10	23-12-11	D40498J	11			TB1301Y	A005	1A		ALL
0038	24		PK		1-7	23-12-11	TB1301Y	A005	1A		D00199B	B14			ALL
0039	22		PA		1-10	23-12-11	GD01302	DC..	1A		D00199B	A02			ALL
0040	22		CQ		2-3	23-42-12	TB1304Y	A003	1A		D41337J	19			YC051-YN260
0041	22		CQ		2-7	23-42-12	TB1304Y	A003	1A		D04181J	1			YC051-YN260
0042	22		CQ		1-9	23-42-12	D04195J	24			TB1304Y	A003	1A		YC051-YN260
0043	22		PA		2-10	23-42-11	D41509J	39			D02639B	B11			ALL
0044	22		G5		3-2	27-62-11	D01040A	D13			D40466J	40			ALL
0045	22		G5		3-2	27-62-11	D01040A	A09			D40466J	41			ALL
0046	22		G5		3-2	27-62-11	D01040A	A11			D40466J	42			ALL
0047	22		G5		3-2	27-62-11	D01040A	D10			D40466J	43			ALL
0049	22		G5		2-11	27-83-11	D40344J	2			D43040J	22			ALL
0051	24		PK		3-1	23-31-04	TB1302Y	B007	1A		D04181J	6			YL951-YL999, YR301-YR328
0052	24		PK		3-1	23-31-04	TB1302Y	B007	1A		D04181J	9			YL951-YL999, YR301-YR328
0054	24		PK		2-7	23-31-06	D41337J	14			D40466J	10			YD158-YN260
0054	24		PK		2-10	44-21-22	D41337J	14			D40466J	10			YN501-YR328
0055	24		PK		2-7	23-31-06	D41337J	28			D40466J	11			YD158-YN260
0055	24		PK		2-10	44-21-22	D41337J	28			D40466J	11			YN501-YR328
0057	24		PK		3-1	31-31-17	D41509J	42			D00199B	D01			ALL
0058	24		PK		1-8	31-31-15	D40488J	13			D43010J	18			ALL

WIRE LIST

D280A108

91-21-11

Section W0130

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0131		286A0131				E001-03	SHELF (continued)									
0059		24		PK		0-7	23-12-11	D00199B	B09			D00199B	C09			YD158-YR328
0060		24		G6		3-3	32-41-11	D40488J	17			D01040B	C01			ALL
0061		24		PK		2-0	32-41-11	D46051J	8			TB1303Y	A003	1A		ALL
0062		22		G5		3-3	32-41-11	D40488J	4			D01040B	C05			ALL
0063		22		PA		2-11	32-41-11	D41400J	12			D01040B	D01			ALL
0064		22		PA		3-0	32-41-11	D41400J	13			D01040A	D01			ALL
0065		22		PA		2-8	32-41-11	D40498J	8			D01040A	D05			ALL
0066		22		PA		2-8	32-41-11	D40498J	10			D01040A	C11			ALL
0067		22		PA		2-9	32-41-11	D43048J	6			D01040A	A15			ALL
0068		22		PA		2-0	32-41-11	D40344J	9			D01040B	B15			ALL
0069		24		PK		2-3	32-42-11	D46051J	9			D01040B	A11			ALL
0070		24		PK		2-4	32-42-11	D46051J	11			D01040A	A04			ALL
0071		24		PK		2-3	32-42-11	D46051J	12			D01040B	C09			ALL
0072		24		PK		3-2	32-42-11	D40466J	2			D01040A	B07			ALL
0073		24		PK		2-8	32-42-11	D41400J	2			TB1303Y	B003	1A		ALL
0074		24		PK		1-7	32-42-11	TB1303Y	B003	1A		D01040B	D04			ALL
0075		24		PK		2-11	32-42-11	D41400J	3			D01040B	D07			ALL
0076		24		PK		2-11	32-42-11	D41400J	4			D01040B	D08			ALL
0077		24		PK		2-11	32-42-11	D41400J	5			D01040B	D12			ALL
0078		24		PK		2-11	32-42-11	D41400J	6			D01040B	D09			ALL
0079		24		PK		2-11	32-42-11	D41400J	7			D01040B	D10			ALL
0080		24		PK		2-11	32-42-11	D41400J	8			D01040B	C10			ALL
0081		24		PK		3-0	32-42-11	D41400J	9			D01040A	D07			ALL
0082		24		PK		2-11	32-42-11	D41400J	10			D01040B	C14			ALL
0083		24		PK		2-11	32-42-11	D41400J	11			D01040B	C03			ALL
0084		24		PK		3-1	32-42-11	D40466J	23			D01040B	D06			ALL
0085		24		PK		3-2	32-42-11	D40466J	24			D01040A	A07			ALL
0086		24		PK		3-1	32-42-11	D40466J	25			D01040B	A02			ALL
0087		24		PK		3-1	32-42-11	D40466J	26			D01040B	B09			ALL
0089		24		PK		2-0	32-42-11	D40344J	23			D01040B	A04			ALL
0090		24		PK		2-0	32-42-11	D40344J	24			D01040B	A07			ALL
0091		24		PK		3-5	32-44-11	D40488J	1			D01040A	D15			ALL
0092		22		G5		1-9	32-64-21	D40466J	3			D41131J	26			ALL
0093		24		PK		2-4	32-41-11	D40498J	18			TB1303Y	A003	1A		ALL
0094		24		PK		1-9	32-41-11	TB1303Y	A003	1A		D01040A	C01			ALL
0095		24		PK		2-6	33-25-11	D46051J	5			D02639B	D11			ALL
0096		24		PK		2-6	33-25-11	D46051J	6			D02639B	C11			ALL
0097		22		PA		2-2	33-27-11	D41831J	3			D02639B	A11			ALL
0104		22		PA		2-6	52-71-12	D40466J	20			D40498J	1			ALL

WIRE LIST

D280A108

91-21-11

Section W0130

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0131	286A0131				E001-03 SHELF (continued)											
0106	22		PA		1-11	32-41-11		GD01304	DC..	1A		D01040A	C06			ALL
0107	22		G5		1-10	32-41-11		GD01304	DC..	1A		D01040B	C02			ALL
0108	22		PA		1-10	32-41-11		GD01304	ST..	1A		D01040B	C13			ALL
0109	24		PK		2-9	32-41-11		D01040A	B03			D43048J	5			ALL
0110	24		G6		3-3	32-41-11		D01040B	A03			D43040J	12			ALL
0111	24		G6		3-1	32-41-11		D01040B	A01			D43010J	2			ALL
0112	24		PK		2-1	32-41-11		D01040A	B01			D40344J	26			ALL
0113	24		PK		3-1	32-42-11		D40466J	1			D01040B	C11			ALL
0114	24		PK		2-11	32-42-11		D41400J	1			D01040B	B07			ALL
0115	24		G6		3-5	32-42-11		D01040A	C08			D40488J	2			ALL
0116	24		G6		3-5	32-42-11		D01040A	A08			D40488J	3			ALL
0117	24		PK		2-7	32-42-11		D01040B	C08			D40498J	4			ALL
0118	24		PK		2-7	32-42-11		D01040B	A08			D40498J	5			ALL
0119	24		PK		3-0	32-42-11		TB1303Y	B003	1A		D43040J	11			ALL
0121	24		PK		3-4	32-42-11		D01040A	B08			D43040J	10			ALL
0122	22		PA		2-6	32-41-11		D40498J	9			D43010J	1			ALL
0123	22		PA		1-11	34-31-11		D40498J	2			D41509J	41			ALL
0124	22		PA		3-0	23-12-11		D04123J	4			D00199B	D05			YC051-YD157
0124	22		PA		3-0	23-12-11		D04123J	11			D00199B	D05			YD158-YR328
0125	20		PA		2-9	23-12-11		D04123J	10			TB1301W	A001	1		YC051-YD157
0129	20		PA		1-9	22-11-12		D40466J	38			D41131J	27			ALL
0131	22		PA		1-1	23-31-06		TB1304Y	A001	1A		TB1304Z	A009	1A		YC051-YD157
0132	22		PA		1-11	23-31-06		TB1302Z	A013	1A		TB1304Y	B001	1A		YC051-YD157
0132	24		PK		3-0	23-12-41		D04123J	10			D00199B	D11			YD158-YR328
0133	22		PA		1-11	23-31-06		TB1304Z	B009	1A		TB1302Z	B009	1A		YC051-YD157
0136	22		PA		1-11	23-31-06		TB1302Y	B001	1A		TB1304Z	A013	1A		YC051-YD157
0138	22		PA		1-8	23-31-06		D02639B	D04			TB1302Y	B001	1A		YC051-YD157
0138	22		PA		2-0	23-31-06		D02639B	D04			TB1304Z	A013	1A		YD158-YN260
0138	22		PA		1-11	44-21-22		D02639B	D04			TB1304Z	A005	1A		YN501-YR328
0140	22		PA		2-7	23-34-01		D40466J	4			D41337J	26			YC051-YN260
0140	22		PA		0-7	44-21-26		D40466J	4			SM00010		S		YN501-YR328
0141	22		PA		2-7	23-34-01		D41337J	27			D40466J	5			YL951-YN260
0142	24		PK		2-4	23-34-01		TB1302Z	B009	1A		D04195J	44			YC051-YD170
0142	22		PA		2-2	23-34-01		TB1302Z	B009	1A		TB1304Y	B021	1A		YL951-YN260
0142	22		PA		2-2	44-21-22		TB1304Y	B021	1A		TB1302Z	B009	1A		YN501-YR328
0143	24		PK		2-5	23-34-01		TB1302Z	A013	1A		D04195J	45			YC051-YD170
0143	22		PA		2-2	23-34-01		TB1302Z	A013	1A		TB1304Y	B019	1A		YL951-YN260
0143	22		PA		2-2	44-21-22		TB1304Y	B019	1A		TB1302Z	A013	1A		YN501-YR328
0144	24		PK		1-11	23-34-01		TB1304Z	B013	1A		D04195J	46			YC051-YD170

WIRE LIST

D280A108

91-21-11

Section W0130

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		Diagram	From			To			Effectivity
	Wire No.	GA	CO TY		Equip	Term		Type	Splice	Equip	Term	Type	Splice	
W0131	286A0131				E001-03 SHELF (continued)									
0144	22		PA		1-5	23-34-01	TB1304Z	B013	1A		TB1304Y	B017	1A	YL951-YN260
0144	22		PA		1-2	44-21-22	TB1304Z	A005	1A		TB1304Z	A013	1A	YN501-YR328
0146	22		GA		3-4	23-34-01	TB1302Z	A009	1A		D40466J	5		YC051-YC059
0146	22		PA		2-7	23-34-01	D41337J	25			D40466J	5		YC060-YD157
0146	22		PA		2-7	23-34-01	D41337J	27			D40466J	5		YD158-YD170
0146	22		PA		0-7	44-21-26	D40466J	46			SM00009		S	YN501-YR328
0147	22		PA		1-7	23-31-06	TB1304Y	B005	1A		D45227J	1		YC051-YD157
0148	22		PA		1-10	23-31-06	TB1304Y	A005	1A		TB1302Y	B001	1A	YC051-YD157
0149	22		PA		3-6	23-31-06	D40488J	22			TB1302Z	A009	1A	YC051-YN260
0149	20		PA		1-7	44-21-22	SM00009		S		D40488J	22		YN501-YR328
0150	22		PA		3-1	23-31-06	TB1304Z	B013	1A		D40488J	23		YC051-YD170
0150	22		PA		3-1	23-31-06	D40488J	23			TB1304Z	B013	1A	YL951-YN260
0150	22		PA		2-11	44-21-22	TB1304Z	B005	1A		D40488J	23		YN501-YR328
0151	22		PA		2-1	23-32-12	D40498J	3			D45227J	14		YC051-YD157
0151	22		PA		2-1	23-32-14	D40498J	3			D45227J	15		YD158-YL999
0151	22		PA		2-1	23-32-14	D45227J	15			D40498J	3		YN231-YN260
0151	22		PA		2-1	44-21-22	D40498J	3			D45227J	15		YN501-YR328
0152	22		PA		2-5	23-32-12	D40498J	6			TB1303Y	B009	1A	YC051-YD157
0152	22		PA		2-1	23-32-14	D40498J	6			D45227J	16		YD158-YL999
0152	22		PA		2-1	23-32-14	D45227J	16			D40498J	6		YN231-YN260
0152	22		PA		2-1	44-21-22	D40498J	6			D45227J	16		YN501-YR328
0153	22		PA		2-1	23-32-12	D40498J	7			D45227J	16		YC051-YD157
0153	22		PA		2-1	23-32-14	D40498J	7			D45227J	14		YD158-YL999
0153	22		PA		2-1	23-32-14	D45227J	14			D40498J	7		YN231-YN260
0153	22		PA		2-1	44-21-22	D40498J	7			D45227J	14		YN501-YR328
0154	22		PA		1-10	23-32-12	D46051J	1			D45227J	6		YC051-YD157
0154	22		PA		1-10	23-32-14	D46051J	1			D45227J	6		YD158-YL999
0154	22		PA		1-10	23-32-14	D45227J	6			D46051J	1		YN231-YN260
0154	22		PA		1-10	44-21-22	D46051J	1			D45227J	6		YN501-YR328
0155	24		PK		1-9	23-31-06	D04195J	50			TB1304Y	A005	1A	YC051-YD157
0155	24		PK		1-11	23-34-01	D04195J	50			TB1304Z	A013	1A	YD158-YD170
0156	22		PA		2-10	23-42-11	D41509J	37			D02639B	D10		YC051-YD157
0164	22		PA		1-9	23-34-01	D45227J	13			TB1304Y	A017	1A	YL951-YN260
0164	22		PA		1-11	44-21-22	D41337J	33			TB1304Y	A019	1A	YN501-YR328
0165	20		PA		2-4	23-11-16	D04195J	55			D40498J	29		YD158-YD170
0168	22		PA		2-11	23-31-06	D41337J	13			D02639B	D09		YD155-YD170
0168	22		PA		2-11	23-31-06	D02639B	D09			D41337J	13		YL951-YN260
0168	22		PA		1-7	44-21-22	SM00012		W		D41337J	13		YN501-YR328
0201	24		PK		2-7	34-53-11	D41509J	1			M01987	1	1A	ALL

WIRE LIST

D280A108

91-21-11

Section W0130

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0131	286A0131			E001-03 SHELF (continued)											
0202	24		PK		2-7	34-53-11	D41509J		2		M01987	2	1A		ALL
0203	24		PK		2-7	34-53-11	D41509J		3		M01987	3	1A		ALL
0204	24		PK		2-7	34-53-11	D41509J		4		M01987	4	1A		ALL
0205	24		PK		2-7	34-53-11	D41509J		5		M01987	5	1A		ALL
0206	24		PK		2-7	34-53-11	D41509J		6		M01987	6	1A		ALL
0207	24		PK		2-7	34-53-11	D41509J		7		M01987	7	1A		ALL
0208	24		PK		2-7	34-53-11	D41509J		8		M01987	8	1A		ALL
0209	24		PK		2-6	34-53-11	D41509J		9		M01987	9	1A		ALL
0210	24		PK		2-6	34-53-11	D41509J		10		M01987	10	1A		ALL
0211	24		PK		2-6	34-53-11	D41509J		11		M01987	11	1A		ALL
0212	24		PK		2-6	34-53-11	D41509J		12		M01987	12	1A		ALL
0213	24		PK		2-6	34-53-11	D41509J		13		M01987	13	1A		ALL
0214	24		PK		2-6	34-53-11	D41509J		14		M01987	14	1A		ALL
0215	24		PK		2-6	34-53-11	D41509J		15		M01987	15	1A		ALL
0216	24		PK		2-6	34-53-11	D41509J		16		M01987	16	1A		ALL
0217	24		PK		2-6	34-53-11	D41509J		17		M01987	17	1A		ALL
0218	24		PK		2-6	34-53-11	D41509J		18		M01987	18	1A		ALL
0219	24		PK		2-6	34-53-11	D41509J		19		M01987	19	1A		ALL
0220	24		PK		2-6	34-53-11	D41509J		20		M01987	20	1A		ALL
0221	24		PK		2-6	34-53-11	D41509J		21		M01987	21	1A		ALL
0222	24		PK		2-6	34-53-11	D41509J		22		M01987	22	1A		ALL
0223	24		PK		2-6	34-53-11	D41509J		23		M01987	23	1A		ALL
0224	24		PK		2-6	34-53-11	D41509J		24		M01987	24	1A		ALL
0225	24		PK		2-6	34-53-11	D41509J		25		M01987	25	1A		ALL
0246	22		PA		2-1	23-32-14	D40498J		25		D45227J	3			YD158-YL999
0246	22		PA		2-1	23-32-14	D45227J		3		D40498J	25			YN231-YN260
0246	22		PA		2-1	44-21-22	D40498J		25		D45227J	3			YN501-YR328
0248	22		PA		2-8	23-32-14	D40466J		18		D45227J	2			YD158-YL999
0248	22		PA		2-8	23-32-14	D45227J		2		D40466J	18			YN231-YN260
0248	22		PA		2-8	44-21-22	D40466J		18		D45227J	2			YN501-YR328
0251	22		PA		0-7	23-34-01	TB1304Y	A017	1A		TB1304Y	A019	1A		YL951-YN260
0251	22		PA		1-5	44-21-22	TB1304Y	B009	1A		TB1304Y	A021	1A		YN501-YR328
0252	22		PA		1-7	23-34-01	TB1304Y	A019	1A		TB1304Y	A021	1A		YL951-YN260
0252	22		PA		1-7	44-21-22	TB1304Y	A021	1A		TB1304Y	A019	1A		YN501-YR328
0253	22		PA		1-4	23-34-01	TB1304Y	A021	1A		TB1304Z	B005	1A		YL951-YN260
0256	22		PA		1-2	23-34-01	TB1304Z	A013	1A		TB1304Z	A005	1A		YL951-YN260
0256	22		PA		1-3	44-21-22	TB1304Z	A013	1A		TB1304Y	A009	1A		YN501-YR328
0257	22		PA		1-7	23-34-01	D45227J		37		TB1304Z	A005	1A		YL951-YN260
0258	22		PA		1-9	23-32-12	TB1303Y	A009	1A		D45227J	15			YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0130

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From			To						
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W0131	286A0131			E001-03 SHELF (continued)												
0260	22	PA			1-9	44-21-22	TB1304Z	B005	1A		D41337J	6			YN501-YR328	
0271	22	PA			1-8	23-34-01	D45227J	1			TB1304Z	A013	1A		YL951-YN260	
0271	22	PA			1-10	44-21-22	D41337J	32			TB1304Z	B013	1A		YN501-YR328	
0301	24	G6			1-9	34-53-21	D41131J	1			M01988	1	1A		ALL	
0302	24	G6			1-9	34-53-21	D41131J	2			M01988	2	1A		ALL	
0303	24	G6			1-9	34-53-21	D41131J	3			M01988	3	1A		ALL	
0304	24	G6			1-9	34-53-21	D41131J	4			M01988	4	1A		ALL	
0305	24	G6			1-9	34-53-21	D41131J	5			M01988	5	1A		ALL	
0306	24	G6			1-9	34-53-21	D41131J	6			M01988	6	1A		ALL	
0307	24	G6			1-9	34-53-21	D41131J	7			M01988	7	1A		ALL	
0308	24	G6			1-9	34-53-21	D41131J	8			M01988	8	1A		ALL	
0309	24	G6			1-8	34-53-21	D41131J	9			M01988	9	1A		ALL	
0310	24	G6			1-8	34-53-21	D41131J	10			M01988	10	1A		ALL	
0311	24	G6			1-8	34-53-21	D41131J	11			M01988	11	1A		ALL	
0312	24	G6			1-8	34-53-21	D41131J	12			M01988	12	1A		ALL	
0313	24	G6			1-8	34-53-21	D41131J	13			M01988	13	1A		ALL	
0314	24	G6			1-8	34-53-21	D41131J	14			M01988	14	1A		ALL	
0315	24	G6			1-8	34-53-21	D41131J	15			M01988	15	1A		ALL	
0316	24	G6			1-8	34-53-21	D41131J	16			M01988	16	1A		ALL	
0317	24	G6			1-8	34-53-21	D41131J	17			M01988	17	1A		ALL	
0318	24	G6			1-8	34-53-21	D41131J	18			M01988	18	1A		ALL	
0319	24	G6			1-8	34-53-21	D41131J	19			M01988	19	1A		ALL	
0320	24	G6			1-8	34-53-21	D41131J	20			M01988	20	1A		ALL	
0321	24	G6			1-8	34-53-21	D41131J	21			M01988	21	1A		ALL	
0322	24	G6			1-8	34-53-21	D41131J	22			M01988	22	1A		ALL	
0323	24	G6			1-8	34-53-21	D41131J	23			M01988	23	1A		ALL	
0324	24	G6			1-8	34-53-21	D41131J	24			M01988	24	1A		ALL	
0325	24	G6			1-8	34-53-21	D41131J	25			M01988	25	1A		ALL	
0392	22	PA			1-4	44-21-22	D02639B	D09			SM00012		W		YN501-YR328	
0435	22	PA			1-10	23-12-11	GD01302	DC..	1A		D00199B	C11			YD158-YD170, YN231-YR328	
0435	22	PA			1-10	23-12-11	D00199B	C11			GD01302	DC..	1A		YL951-YL999	
0447	20	PA			0-7	44-21-10	D40466J	45			SM00009		S		YN501-YR328	
0449	20	PA			2-10	44-21-10	D41337J	27			SM00009		S		YN501-YR328	
0450	20	PA			0-7	44-21-10	D40466J	44			SM00010		S		YN501-YR328	
0454	20	PA			2-10	44-21-10	D41337J	26			SM00010		S		YN501-YR328	
0478	22	PA			1-5	44-21-22	SM00012		W		D45227J	1			YN501-YR328	
0482	20	PA			2-10	44-21-26	D40466J	16			D41337J	37			YN501-YR328	
0483	22	PA			1-9	44-21-26	D41337J	36			TB1304Z	A005	1A		YN501-YR328	

WIRE LIST

D280A108

91-21-11

Section W0130

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0131	286A0131			E001-03 SHELF (continued)											
0523	22		PA		2-7	23-42-12	TB1304Y	A003	1A		D04181J	1			YR315-YR328
0525	22		PA		1-9	23-42-12	TB1304Y	A003	1A		D04195J	24			YR315-YR328
0526	22		PA		1-8	23-42-12	TB1304Y	A003	1A		D41337J	19			YR315-YR328
1501R	22		PH		2-3	26-11-21	D40810J		19		D40344J	18			ALL
1502R	22		PH		2-3	26-11-21	D40810J		26		D40344J	31			ALL
1503R	22		PH		2-3	26-11-21	D40810J		27		D40344J	30			ALL
1504R	22		PH		2-3	26-11-21	D40810J		28		D40344J	29			ALL
1505R	22		PH		2-3	26-11-21	D40810J		29		D40344J	28			ALL
1506R	22		PH		2-3	26-11-21	D40810J		30		D40344J	17			ALL
1507R	20		PH		2-11	26-12-11	D43040J		14		D40344J	20			ALL
1508R	20		PH		2-11	26-12-11	D40344J		21		D43040J	15			ALL
1509R	20		PH		2-0	26-21-11	D40810J		25		D43048J	7			ALL
1510R	20		PH		2-0	26-21-11	D40810J		20		D43048J	8			ALL
1511R	20		PH		1-11	26-21-11	D40810J		21		D40498J	13			ALL
1512R	20		PH		1-11	26-21-11	D40810J		35		D40498J	14			ALL
1513R	20		PH		1-11	26-21-11	D40810J		33		D40498J	15			ALL
1514R	20		PH		1-11	26-21-11	D40810J		24		D40498J	26			ALL
1515R	20		PH		1-11	26-21-11	D40810J		34		D40498J	27			ALL
1516R	20		PH		1-11	26-21-11	D40810J		22		D40498J	28			ALL
1517R	20		PH		2-11	26-12-11	D40344J		19		D43040J	21			ALL
2001B	24		PL	EA	3-0	23-31-01	D41337J		11		TB1302Y	A007	1A		YC051-YN260
2001B	24		PL	EA	2-6	23-31-01	D41337J		11		TB1302Z	A021	1A		YN501-YR328
2001R	24		PL	EA	0-0	23-31-01	D41337J		10		TB1302Z	B013	1A		ALL
2002B	24		PL	EB	3-3	23-31-01	D04181J		8		TB1302Y	A007	1A		YC051-YN260
2002B	24		PL	EB	3-5	23-31-01	D04181J		8		TB1302Z	A021	1A		YN501-YR328
2002R	24		PL	EB	0-0	23-31-01	D04181J		7		TB1302Z	B013	1A		ALL
2003B	24		PL	EC	2-11	23-31-01	D04149J		3		TB1302Y	A001	1A		ALL
2003R	24		PL	EC	0-0	23-31-01	D04149J		2		TB1302Y	B003	1A		ALL
2004B	24		PL	ED	2-4	23-31-02	D02639B		B09		D04195J	10			ALL
2004R	24		PL	ED	0-0	23-31-02	D02639B		A09		D04195J	9			ALL
2005B	24		PL	EE	2-4	23-31-02	D02639B		D13		D04195J	8			ALL
2005R	24		PL	EE	0-0	23-31-02	D02639B		C13		D04195J	7			ALL
2006B	22		PB	EF	2-6	23-31-02	TB1302Z		B017	1A	D04195J	12			ALL
2006R	22		PB	EF	0-0	23-31-02	TB1302Z		A017	1A	D04195J	11			ALL
2007B	22		PB	EG	1-11	23-31-02	D02639B		B15		TB1302Z	B017	1A		ALL
2007R	22		PB	EG	0-0	23-31-02	D02639B		A15		TB1302Z	A017	1A		ALL
2008B	22		PB	EH	2-4	23-31-02	D02639B		B14		D04195J	6			ALL
2008R	22		PB	EH	0-0	23-31-02	D02639B		A14		D04195J	5			ALL
2009B	24		PL	EI	2-3	23-31-02	TB1302Y		A001	1A	D04195J	14			ALL

WIRE LIST

D280A108

91-21-11

Section W0130

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Diagram	From				To				Effectivity		
	Wire No.	GA	CO TY			Fam	FT-IN	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W0131	286A0131			E001-03 SHELF (continued)												
2009R	24	PL	EI		0-0	23-31-02	TB1302Y	B003	1A			D04195J	13			ALL
2010B	22	PB	EJ		2-6	23-31-04	TB1302Z	B017	1A			D04195J	17			ALL
2010R	22	PB	EJ		0-0	23-31-04	TB1302Z	A017	1A			D04195J	16			ALL
2011B	24	PL	EK		2-11	23-31-06	D02639B	B05				D41337J	5			YC051-YN260
2011B	24	PL	EK		2-4	44-21-22	D02639B	B05				D41337J	5			YN501-YR313
2011B	24	Y2	EK		2-4	44-21-22	D02639B	B05				D41337J	5			YR314-YR328
2011R	24	PL	EK		0-0	23-31-06	D02639B	A05				D41337J	4			YC051-YN260
2011R	24	PL	EK		0-0	44-21-22	D02639B	A05				D41337J	4			YN501-YR313
2011R	24	Y2	EK		0-0	44-21-22	D02639B	A05				D41337J	4			YR314-YR328
2011Z			EK		0-0	44-21-22	D02639B	DED				D41337J			AF	YR314-YR328
2012B	24	PL	EL		2-9	23-31-06	D40488J		14			D41337J	8			YC051-YD170
2012B	24	PL	EL		2-9	23-31-06	D41337J		8			D40488J	14			YL951-YN260
2012B	24	PL	EL		3-0	44-21-22	D40488J		14			D41337J	8			YN501-YR313
2012B	24	Y2	EL		3-0	44-21-22	D40488J		14			D41337J	8			YR314-YR328
2012R	24	PL	EL		0-0	23-31-06	D40488J		6			D41337J	7			YC051-YD170
2012R	24	PL	EL		0-0	23-31-06	D41337J		7			D40488J	6			YL951-YN260
2012R	24	PL	EL		0-0	44-21-22	D40488J		6			D41337J	7			YN501-YR313
2012R	24	Y2	EL		0-0	44-21-22	D40488J		6			D41337J	7			YR314-YR328
2012Z			EL		0-0	44-21-22	D40488J			AG		D41337J			AF	YR314-YR328
2015B	22	X2	EP		1-5	32-64-12	D43010J		12			D40466J	8			ALL
2015R	22	X2	EP		0-0	32-64-12	D43010J		11			D40466J	9			ALL
2015Z			EP		0-0	32-64-12	D43010J	DED				D40466J	DED			ALL
2016B	22	X2	EQ		1-5	32-64-12	D43010J		10			D40466J	6			ALL
2016R	22	X2	EQ		0-0	32-64-12	D43010J		9			D40466J	7			ALL
2016Z			EQ		0-0	32-64-12	D43010J	DED				D40466J	DED			ALL
2018B	24	Y2	ES		1-5	32-31-12	D40466J		14			D43010J	15			ALL
2018R	24	Y2	ES		0-0	32-31-12	D40466J		15			D43010J	13			ALL
2018Z			ES		0-0	32-31-12	D40466J	DED				D43010J	DED			ALL
2019B	24	PL	ET		3-1	32-42-11	D01040B	A09				D43010J	4			ALL
2019R	24	PL	ET		0-0	32-42-11	D01040B	B08				D43010J	3			ALL
2020B	24	PL	EU		3-3	32-42-11	D01040A	B10				D43010J	6			ALL
2020R	24	PL	EU		0-0	32-42-11	D01040A	A10				D43010J	5			ALL
2021B	24	PL	EV		3-4	32-42-11	D01040A	C07				D43040J	17			ALL
2021R	24	PL	EV		0-0	32-42-11	D01040B	A10				D43040J	16			ALL
2023B	24	PL	EX		1-10	23-31-01	TB1302Y	A007	1A			D02639B	B02			YC051-YN260
2023B	24	PL	EX		2-0	23-31-01	TB1302Z	A021	1A			D02639B	B02			YN501-YR328
2023R	24	PL	EX		0-0	23-31-01	TB1302Z	B013	1A			D02639B	A02			ALL
2024B	24	PL	EY		1-8	23-31-01	TB1302Y	A001	1A			D02639B	B01			ALL
2024R	24	PL	EY		0-0	23-31-01	TB1302Y	B003	1A			D02639B	A01			ALL

WIRE LIST

D280A108

91-21-11

Section W0130

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0131	286A0131			E001-03 SHELF (continued)											
2025B	24	PL	EZ		3-3	23-31-01	D04181J		12		TB1302Y	A007	1A		YL951-YL999
2025B	24	PL	EZ		3-5	23-31-01	D04181J		12		TB1302Z	A021	1A		YR301-YR328
2025R	24	PL	EZ		0-0	23-31-01	D04181J		11		TB1302Z	B013	1A		YL951-YL999, YR301-YR328
2026B	24	PL	FA		3-6	23-31-06	D02639B		A04		D40488J		19		YC051-YD157
2026B	24	PL	FA		3-6	23-31-06	D02639B		B04		D40488J		19		YD158-YN260
2026B	24	PL	FA		3-6	44-21-22	D02639B		B04		D40488J		19		YN501-YR313
2026B	24	Y2	FA		3-6	44-21-22	D02639B		B04		D40488J		19		YR314-YR328
2026R	24	PL	FA		0-0	23-31-06	D02639B		B04		D40488J		18		YC051-YD157
2026R	24	PL	FA		0-0	23-31-06	D02639B		A04		D40488J		18		YD158-YN260
2026R	24	PL	FA		0-0	44-21-22	D02639B		A04		D40488J		18		YN501-YR313
2026R	24	Y2	FA		0-0	44-21-22	D02639B		A04		D40488J		18		YR314-YR328
2026Z			FA		0-0	44-21-22	D02639B		DED		D40488J			AG	YR314-YR328
2027B	24	PL	FB		2-10	23-31-06	D45227J		5		D40488J		21		YC051-YD157
2027B	22	PB	FB		2-5	44-21-26	D41337J		39		TB1302Z	B017	1A		YN501-YR328
2027R	24	PL	FB		0-0	23-31-06	D45227J		4		D40488J		20		YC051-YD157
2027R	22	PB	FB		0-0	44-21-26	D41337J		38		TB1302Z	A017	1A		YN501-YR328
2029B	22	PB	FD		2-5	44-21-22	D41337J		30		TB1302Z	B017	1A		YN501-YR328
2029R	22	PB	FD		0-0	44-21-22	D41337J		29		TB1302Z	A017	1A		YN501-YR328
2325B	24	W9	AX		3-0	23-31-06	D45227J		11		D41337J		28		YC051-YC052
2501B	24	Y2	AA		3-0	23-12-11	D04123J		2		D00199B		B07		YC051-YD157
2501B	24	Y2	AA		3-0	23-12-41	D04123J		8		D00199B		B07		YD158-YR328
2501R	24	Y2	AA		0-0	23-12-11	D04123J		1		D00199B		A07		YC051-YD157
2501R	24	Y2	AA		0-0	23-12-41	D04123J		7		D00199B		A07		YD158-YR328
2501Z			AA		0-0	23-12-11	D04123J		3		GB01301		ST..	1A	YC051-YD157
2501Z			AA		0-0	23-12-41	D04123J		9		GB01301		ST..	1A	YD158-YR328
2502B	24	M5	AB		2-8	23-12-11	D04195J		32		D00199B		B01		ALL
2502R	24	M5	AB		0-0	23-12-11	D04195J		31		D00199B		A01		ALL
2502ZI			AB		0-0	23-12-11	D04195J		33		D00199B		DED		ALL
2502ZO			AB		0-0	23-12-11	D04195J		39		GB01301		ST..	1A	ALL
2503B	24	M5	AC		2-8	23-12-11	D04195J		29		D00199B		B15		ALL
2503R	24	M5	AC		0-0	23-12-11	D04195J		28		D00199B		A15		ALL
2503ZI			AC		0-0	23-12-11	D04195J		30		D00199B		DED		ALL
2503ZO			AC		0-0	23-12-11	D04195J		27		GB01301		ST..	1A	ALL
2504B	24	M5	AD		2-8	23-22-11	D00199B		B13		D04195J		22		ALL
2504R	24	M5	AD		0-0	23-22-11	D00199B		A13		D04195J		21		ALL
2504ZI			AD		0-0	23-22-11	D00199B		DED		D04195J		23		ALL
2504ZO			AD		0-0	23-22-11	GB01301		ST..	1A	D04195J		41		ALL
2506B	24	Y2	AF		2-6	23-34-01	D04195J		48		TB1302Z	B017	1A		YC051-YD170

WIRE LIST

D280A108

91-21-11

Section W0130

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0131		286A0131			E001-03 SHELF (continued)											
2506B		22		X2	AF	2-3	23-34-01	D45227J	24			TB1302Z	B017	1A		YL951-YN260
2506R		24		Y2	AF	0-0	23-34-01	D04195J	47			TB1302Z	A017	1A		YC051-YD170
2506R		22		X2	AF	0-0	23-34-01	D45227J	25			TB1302Z	A017	1A		YL951-YN260
2506Z					AF	0-0	23-34-01	D04195J	49			TB1302Z	DED			YC051-YD170
2506Z					AF	0-0	23-34-01	D45227J	26			TB1302Z	DED			YL951-YN260
2508B		24		Y2	AH	2-8	34-21-13	D41509J	30			D01040A	D12			ALL
2508R		24		Y2	AH	0-0	34-21-13	D41509J	29			D01040A	D11			ALL
2508Z					AH	0-0	34-21-13	D41509J	31			GB01303	ST..	1A		ALL
2509B		24		Y2	AI	2-6	34-21-23	D41509J	33			D01040B	D14			ALL
2509R		24		Y2	AI	0-0	34-21-23	D41509J	32			D01040B	D13			ALL
2509Z					AI	0-0	34-21-23	D41509J	34			GB01303	ST..	1A		ALL
2510B		24		Y2	AJ	2-1	32-41-11	D01040A	B06			D40344J	7			ALL
2510R		24		Y2	AJ	0-0	32-41-11	D01040A	B05			D40344J	6			ALL
2510Z					AJ	0-0	32-41-11	GB01303	ST..	1A		D40344J	8			ALL
2511B		24		Y2	AK	3-4	32-41-11	D01040A	B13			D43040J	2			ALL
2511R		24		Y2	AK	0-0	32-41-11	D01040A	B12			D43040J	1			ALL
2511Z					AK	0-0	32-41-11	GB01303	ST..	1A		D43040J	3			ALL
2512B		24		Y2	AL	3-1	32-41-11	D01040B	A13			D43010J	8			ALL
2512R		24		Y2	AL	0-0	32-41-11	D01040B	A12			D43010J	7			ALL
2512Z					AL	0-0	32-41-11	GB01303	ST..	1A		D43010J	17			ALL
2513B		24		Y2	AM	2-7	32-41-11	D01040B	A06			D40498J	20			ALL
2513R		24		Y2	AM	0-0	32-41-11	D01040B	A05			D40498J	19			ALL
2513Z					AM	0-0	32-41-11	GB01303	ST..	1A		D40498J	21			ALL
2514B		24		Y2	AN	3-4	32-42-11	D01040A	D09			D43040J	19			ALL
2514R		24		Y2	AN	0-0	32-42-11	D01040A	C09			D43040J	18			ALL
2514Z					AN	0-0	32-42-11	GB01303	ST..	1A		D43040J	20			ALL
2519B		24		Y2	AT	3-0	23-12-41	D04123J	2			D00199B	B11			YD158-YD170, YN501-YR328
2519B		24		Y2	AT	3-0	23-12-41	D00199B	B11			D04123J	2			YL951-YN260
2519R		24		Y2	AT	0-0	23-12-41	D04123J	1			D00199B	A11			YD158-YD170, YN501-YR328
2519R		24		Y2	AT	0-0	23-12-41	D00199B	A11			D04123J	1			YL951-YN260
2519Z					AT	0-0	23-12-41	D04123J	3			GB01301	ST..	1A		YD158-YD170, YN501-YR328
2519Z					AT	0-0	23-12-41	GB01301	ST..	1A		D04123J	3			YL951-YN260
2522B		24		Y2	AW	1-8	29-32-11	D40498J	24			D43048J	4			ALL
2522R		24		Y2	AW	0-0	29-32-11	D40498J	23			D43048J	3			ALL
2522Z					AW	0-0	29-32-11	D40498J	22			D43048J	2			ALL
2523B		24		W9	AX	2-2	23-31-06	D45227J	11			D41337J	28			YC053-YD157

WIRE LIST

D280A108

91-21-11

Section W0130

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W0131	286A0131	E001-03 SHELF (continued)													
2523W	24	W9	AX	0-0	23-31-06	D45227J		10	D41337J	27				YC051-YD157	
2523Z			AX	0-0	23-31-06	D45227J		12	D41337J	29				YC051-YD157	
2525B	24	Y2	AZ	3-0	23-12-11	D04123J		5	D00199B	D14				YD158-YR328	
2525R	24	Y2	AZ	0-0	23-12-11	D04123J		4	D00199B	C14				YD158-YR328	
2525Z			AZ	0-0	23-12-11	D04123J		6	GB01301	ST..	1A			YD158-YR328	
2526B	24	Y2	BA	3-1	23-31-06	D04195J		53	D40488J	21				YD158-YD170	
2526B	24	Y2	BA	2-10	23-31-06	D40488J		21	D45227J	5				YL951-YN260	
2526B	24	Y2	BA	3-0	44-21-22	D41337J		41	D40488J	21				YN501-YR328	
2526R	24	Y2	BA	0-0	23-31-06	D04195J		52	D40488J	20				YD158-YD170	
2526R	24	Y2	BA	0-0	23-31-06	D40488J		20	D45227J	4				YL951-YN260	
2526R	24	Y2	BA	0-0	44-21-22	D41337J		40	D40488J	20				YN501-YR328	
2526Z			BA	0-0	23-31-06	D04195J		54	D40488J	DED				YD158-YD170	
2526Z			BA	0-0	23-31-06	D40488J	DED		D45227J	9				YL951-YN260	
2526Z			BA	0-0	44-21-22	D41337J		42	D40488J	DED				YN501-YR313	
2526Z			BA	0-0	44-21-22	D41337J			D40488J			AG		YR314-YR328	
2531B	24	Y2	BF	3-7	23-27-37	D00199B	B12	VP	D41131J	32				YD158-YD170	
2531B	24	Y2	BF	3-7	23-27-37	D41131J	32	VP	D00199B	B12	VP			YL951-YR328	
2531R	24	Y2	BF	0-0	23-27-37	D00199B	A12	VP	D41131J	31				YD158-YD170	
2531R	24	Y2	BF	0-0	23-27-37	D41131J	31		D00199B	A12	VP			YL951-YR328	
2531Z			BF	0-0	23-27-37	D00199B	DED		D41131J	33				YD158-YD170	
2531Z			BF	0-0	23-27-37	D41131J	33		D00199B	DED				YL951-YR328	
2532B	24	Y6	BG	3-7	23-27-37	D00199B	D10	VP	D41131J	29				YD158-YD170	
2532B	24	Y2	BG	3-7	23-27-37	D41131J	29		D00199B	D10	VP			YL951-YR328	
2532R	24	Y6	BG	0-0	23-27-37	D00199B	C10	VP	D41131J	28				YD158-YD170	
2532R	24	Y2	BG	0-0	23-27-37	D41131J	28		D00199B	C10	VP			YL951-YR328	
2532Z			BG	0-0	23-27-37	D00199B	DED		D41131J	30				YD158-YD170	
2532Z			BG	0-0	23-27-37	D41131J	30		D00199B	DED				YL951-YR328	
3501B	24	Y3	HA	2-7	23-42-12	TB1303Y	A007	1A	D04149J	5				ALL	
3501R	24	Y3	HA	0-0	23-42-12	TB1303Y	B007	1A	D04149J	4				ALL	
3501Y	24	Y3	HA	0-0	23-42-12	TB1303Y	A005	1A	D04149J	6				ALL	
3501Z			HA	0-0	23-42-12	TB1303Y	B005	1A	D04149J	7				ALL	
3502B	24	Y3	HB	2-5	23-42-12	TB1303Y	A007	1A	D41337J	17				YC051-YN260	
3502B	24	Y3	HB	1-10	23-42-12	TB1303Y	A007	1A	D41337J	17				YN501-YR328	
3502R	24	Y3	HB	0-0	23-42-12	TB1303Y	B007	1A	D41337J	16				ALL	
3502Y	24	Y3	HB	0-0	23-42-12	TB1303Y	A005	1A	D41337J	18				ALL	
3502Z			HB	0-0	23-42-12	TB1303Y	B005	1A	D41337J	15				ALL	
3503B	24	Y3	HC	2-9	23-42-12	TB1303Y	A007	1A	D04181J	3				ALL	
3503R	24	Y3	HC	0-0	23-42-12	TB1303Y	B007	1A	D04181J	2				ALL	
3503Y	24	Y3	HC	0-0	23-42-12	TB1303Y	A005	1A	D04181J	4				ALL	

WIRE LIST

D280A108

91-21-11

Section W0130

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0131	286A0131			E001-03 SHELF (continued)											
3503Z				HC	0-0	23-42-12	TB1303Y	B005	1A		D04181J	5			ALL
3504B	24		Y3	HD	1-11	23-42-12	D04195J	36			TB1303Y	A007	1A		ALL
3504R	24		Y3	HD	0-0	23-42-12	D04195J	35			TB1303Y	B007	1A		ALL
3504Y	24		Y3	HD	0-0	23-42-12	D04195J	37			TB1303Y	A005	1A		ALL
3504Z				HD	0-0	23-42-12	D04195J	38			TB1303Y	B005	1A		ALL
FRAF					0-0	44-21-22	D41337J			AF	D41337J	42			YR314-YR328
FRAG					0-0	44-21-22	D40488J			AG	D40488J	11			YR314-YR328
W0132	286A0132			EMERGENCY AISLE LIGHTS - LED											
0001	20		PA		3-10	33-51-12	D14816	A			D14814	A			YN501-YR328
0002	20		PA		3-10	33-51-12	D14816	B			D14814	B			YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0130

Page 13 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W0141	286A0141				E1-4 SHELF - RIGHT											
0002	22		G5		4-0	22-11-11		D10137B	E11			D41129P	2			ALL
0003	20		G5		3-6	22-11-11		D40047P	44			TB1401Y	A001	1A		ALL
0004	20		G5		3-6	22-11-11		D40047P	45			TB1401Y	B001	1A		ALL
0005	20		G5		3-6	22-11-11		D40047P	46			TB1401Y	A003	1A		ALL
0006	22		G5		2-1	22-11-11		D10137C	F05			GD01401	AC..	1A		ALL
0007	22		G5		3-9	22-11-11		D10137C	G05			D40047P	38			ALL
0008	22		G5		4-1	22-11-11		D10137B	D01			D08019P	14			ALL
0009	22		G5		4-1	22-11-11		D10137B	H09			D08019P	15			ALL
0010	22		G5		3-8	22-11-11		D08019P	7			TB1401Y	A001	1A		ALL
0011	22		G5		1-9	22-11-11		D10137B	B01			TB1401Y	A001	1A		ALL
0012	22		G5		3-8	22-11-11		D08019P	6			TB1401Y	B001	1A		ALL
0013	22		G5		1-9	22-11-11		D10137B	H01			TB1401Y	B001	1A		ALL
0014	22		G5		3-8	22-11-11		D08019P	23			TB1401Y	A003	1A		ALL
0015	22		G5		1-9	22-11-11		D10137B	F01			TB1401Y	A003	1A		ALL
0016	22		G5		4-7	22-11-11		D10137B	H14			D40490P	2			ALL
0017	22		G5		4-1	22-11-11		D10137A	H01			D41129P	5			ALL
0018	22		G5		4-1	22-11-11		D10137A	B01			D41129P	4			ALL
0019	22		G5		4-1	22-11-11		D10137A	F01			D41129P	3			ALL
001CO				ZC	0-0	34-31-21		D10721C	=C12			D02123	=C1			ALL
001CX			0F	ZC	3-11	34-31-21		D10721C	12	DN		D02123	=A1			ALL
0021	22		G5		4-0	22-11-12		D10137B	K01			D41129P	6			ALL
0022	22		G5		4-1	22-11-12		D10137A	K01			D41129P	7			ALL
0023	20		G5		3-10	22-11-12		D46031P	2			TB1402Z	B001	1A		ALL
0024	20		G5		4-1	22-11-12		D46031P	4			TB1402Y	A013	1A		YC051-YD155
0024	20		G5		4-1	22-11-12		D46031P	1			TB1402Y	A013	1A		YD157-YR328
0025	20		G5		3-11	22-11-12		D08019P	3			TB1402Z	B001	1A		ALL
0026	20		G5		3-11	22-11-12		D08019P	9			TB1402Z	B001	1A		ALL
0027	20		G5		3-10	22-11-12		D05971P	11			TB1402Z	B001	1A		ALL
0028	22		G5		4-1	22-11-12		D10137B	K07			D05971P	12			ALL
0029	20		G5		4-8	22-11-12		D40490P	18			TB1402Y	A013	1A		ALL
002CO				ZD	0-0	34-51-21		D03625C	=C1			D03787	=C1			ALL
002CX			0F	ZD	4-1	34-51-21		D03625C	1	DN		D03787	=A1			ALL
0030	22		G5		4-9	22-11-12		D10137A	B03			D40490P	19			ALL
0031	22		G5		3-11	22-11-12		D10137B	J05			D40047P	34			ALL
0032	20		G5		3-5	22-11-12		D04077P	20			TB1402Z	B001	1A		ALL
0033	20		G5		3-2	22-11-12		D04077P	21			TB1401Y	A005	1A		ALL
0034	20		G5		3-9	22-11-12		D40047P	6			TB1402Z	B001	1A		YC051-YD155
0034	20		G5		1-11	22-11-12		D40047P	6			D46031P	5			YD157-YR328
0035	22		G5		1-9	22-11-12		D10137B	B13			TB1401Y	A005	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0140

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0141		286A0141				E1-4 SHELF - RIGHT (continued)										
0036		20		G5		3-7	22-11-12	D40047P		7		TB1401Y	A005	1A		ALL
0037		20		G5		3-7	22-11-12	D40047P		8		TB1401Y	B005	1A		ALL
0038		22		G5		1-10	22-11-12	D10137A		B13		TB1401Y	B005	1A		ALL
0039		20		G5		3-9	22-11-12	D04081P		1		TB1401Y	B005	1A		ALL
0040		20		G5		4-1	22-11-12	D04081P		2		TB1402Z	A009	1A		ALL
0041		20		G5		1-1	22-11-12	TB1402Z		B001	1A	TB1402Z	A009	1A		ALL
0042		22		G5		1-10	22-11-12	D10137B		F03		TB1402Z	A009	1A		ALL
0043		20		G5		4-6	22-11-12	D40490P		10		TB1402Z	A009	1A		ALL
0044		22		G5		4-9	22-11-12	D10137A		J10		D40490P		11		ALL
0045		24		G6		4-0	22-11-14	D45123P		8		TB1401Y	B007	1A		ALL
0046		22		G5		1-10	22-11-14	D10137A		F04		TB1401Y	B007	1A		ALL
0047		22		G5		3-8	22-11-14	D05971P		5		TB1401Y	B007	1A		ALL
0048		22		G5		4-5	22-11-14	D05971P		6		GD01401	DC..	1A		ALL
0049		22		G5		2-3	22-11-14	D10137B		C01		GD01401	DC..	1A		ALL
004CO					ZF	0-0	34-58-21	D42943P		= C1		D10721A	= C2			YC051-YC052, YL951-YR328
004CO					ZF	0-0	34-58-21	D10721A		= C2		D42943P	= C1			YC053-YD170
004CX				0F	ZF	4-7	34-58-21	D42943P		= A1		D10721A		2		YC051-YC052, YL951-YR328
004CX				0F	ZF	4-7	34-58-21	D10721A		2		D42943P	= A1			YC053-YD170
0050		22		G5		4-0	22-11-11	D10137A		E11		D40047P		5		ALL
0051		20		G5		1-7	22-11-11	D10137C		51		TB1401Y	B003	1A		YC051-YD155
0052		20		G5		1-7	22-11-11	D10137C		52		TB1401Y	B003	1A		YC051-YD155
0053		20		G5		3-8	22-11-11	D46031P		3		TB1401Y	B003	1A		YC051-YD155
0053		20		G5		3-11	22-11-11	D46031P		3		D10137C		51		YD157-YR328
0056		20		G5		2-1	22-11-11	D10137C		56		GD01401	DC..	1A		ALL
0057		20		G5		2-1	22-11-11	D10137C		57		GD01401	DC..	1A		ALL
0058		20		G5		2-1	22-11-11	D10137C		58		GD01401	DC..	1A		ALL
0059		20		G5		2-1	22-11-11	D10137C		59		GD01401	ST..	1A		ALL
005CO					ZE	0-0	34-31-21	D10721C		= C13		D04027P	= C1			ALL
005CX				0F	ZE	4-4	34-31-21	D10721C		13	DN	D04027P	= A1			ALL
0060		22		G5		3-9	22-11-18	D10137C		K05		D40047P		40		ALL
0061		22		G5		3-8	22-11-18	D41129P		16		TB1401Y	A009	1A		ALL
0062		22		G5		1-10	22-11-18	D10137B		G07		TB1401Y	A009	1A		ALL
0063		22		G5		4-1	22-11-18	D45123P		10		TB1401Y	A009	1A		ALL
0064		22		G5		2-3	22-11-18	D10721B		F15		TB1401Y	A009	1A		ALL
0065		22		X1	BN	3-7	22-11-31	D10137B		D13		D04077P		16		ALL
0065Z					BN	0-0	22-11-31	GB01402		ST..	1A	D04077P	S/R			ALL
0066		22		X1	BO	1-10	22-11-31	D10137B		F13		TB1401Y	B009	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0140

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To
Wire No.	GA CO TY	Fam FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice Effectivity
W0141	286A0141	E1-4 SHELF - RIGHT (continued)		
0066Z		BO	0-0 22-11-31 GB01402 ST.. 1A	GB01401 ST.. 1A ALL
0067	22 X1	BP	3-3 22-11-31 D04077P 17	TB1401Y B009 1A ALL
0067Z		BP	0-0 22-11-31 D04077P S/R	GB01401 ST.. 1A ALL
0068	20 X1	BQ	3-9 22-11-31 D08019P 4	TB1401Y B009 1A ALL
0068Z		BQ	0-0 22-11-31 D08019P S/R	GB01401 ST.. 1A ALL
0069	24 G6		4-3 22-11-75 D10137A A08	D41463P 18 ALL
0070	24 G6		4-3 22-11-75 D10137A B08	D41463P 19 ALL
0071	24 G6		4-3 22-11-75 D10137A E07	D41463P 20 ALL
0072	24 G6		4-3 22-11-75 D10137A G08	D41463P 21 ALL
0073	24 G6		4-3 22-11-75 D10137A F08	D41463P 22 ALL
0074	24 G6		4-3 22-11-75 D10137A G07	D41463P 23 ALL
0075	24 G6		4-3 22-11-75 D10137A H06	D41463P 24 ALL
0076	24 G6		4-3 22-11-75 D10137A C08	D41463P 25 ALL
0077	24 G6		4-3 22-11-75 D10137A D08	D41463P 26 ALL
0078	24 G6		4-3 22-11-75 D10137A E08	D41463P 27 ALL
0079	24 G6		4-3 22-11-75 D10137A J07	D41463P 28 ALL
0080	24 G6		4-3 22-11-75 D10137A J08	D41463P 29 ALL
0082	24 G6		4-3 22-11-75 D10137A F07	D41463P 31 ALL
0083	24 G6		4-3 22-11-75 D10137A H08	D41463P 32 ALL
0085	24 G6		4-3 22-11-75 D10137A K08	D41463P 33 ALL
0086	22 G5		2-3 22-11-75 D10137B A01	GD01401 DC.. 1A ALL
0087	22 G5		2-3 22-11-75 D10137B A05	GD01401 DC.. 1A ALL
0089	22 X1	BR	4-3 22-12-41 D10137A D13	D04081P 5 ALL
0089Z		BR	0-0 22-12-41 GB01401 ST.. 1A	D04081P DED ALL
0090	22 X1	BS	2-0 22-12-41 D10137A F13	TB1401Y A015 1A ALL
0090Z		BS	0-0 22-12-41 GB01401 ST.. 1A	GB01401 ST.. 1A ALL
0091	20 X1	BT	3-11 22-12-41 D04081P 6	TB1401Y A015 1A ALL
0091Z		BT	0-0 22-12-41 D04081P DED	GB01401 ST.. 1A ALL
0092	20 X1	BU	3-10 22-12-41 D08019P 16	TB1401Y A015 1A ALL
0092Z		BU	0-0 22-12-41 D08019P S/R	GB01401 ST.. 1A ALL
0093	22 G5		3-10 22-13-11 D10137C D03	D41129P 8 ALL
0094	22 G5		3-10 22-13-11 D10137C B03	D41129P 9 ALL
0095	22 G5		4-0 22-13-11 D10137C H02	D41463P 37 ALL
0096	22 G5		4-5 22-13-11 D10137C D02	D04311P 1 ALL
0097	22 G5		3-9 22-13-11 D10137C B02	D40047P 32 ALL
0098	22 G5		3-9 22-13-11 D10137C F02	D40047P 23 ALL
0099	22 G5		3-10 22-13-11 D10137C K03	D41129P 10 ALL
0100	22 G5		3-10 22-13-11 D10137C G02	D41129P 11 ALL
0101	22 G5		3-10 22-13-11 D10137C H03	D41129P 12 ALL

WIRE LIST

D280A108

91-21-11
Section W0140
Page 3
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0141		286A0141				E1-4 SHELF - RIGHT (continued)									
	0102	22	G5		3-10	22-13-11	D10137C	A03			D41129P	13			ALL
	0103	22	G5		3-10	22-13-11	D10137C	J02			D41129P	14			ALL
	0104	22	CQ		4-0	22-14-11	D10137B	D07			D41129P	15			ALL
	0105	22	G5		3-10	22-14-11	D10137C	K02			D41129P	17			ALL
	0106	22	CQ		2-0	22-14-11	D10137B	B07			TB1401Y	A017	1A		ALL
	0107	22	CQ		3-9	22-14-11	D40047P	15			TB1401Y	A017	1A		ALL
	0108	20	CQ		3-9	22-14-11	D40047P	24			TB1401Y	B017	1A		ALL
	0109	20	CQ		1-10	22-14-11	D10137C	54			TB1401Y	B017	1A		ALL
	0110	20	CQ		1-10	22-14-11	D10137C	55			TB1401Y	B017	1A		YC051-YD155
	0111	22	G5		2-0	22-14-11	D10137A	E05			TB1401Y	B015	1A		ALL
	0112	22	G5		4-5	22-14-11	D04311P	4			TB1401Y	B015	1A		ALL
	0113	22	G5		4-7	22-14-11	D10137B	G05			D04311P	5			ALL
	0114	22	CQ		4-5	22-14-11	D04311P	11			TB1401Y	A017	1A		ALL
	0115	20	CQ		4-5	22-14-11	D04311P	6			TB1401Y	B017	1A		ALL
	0116	22	G5		3-10	22-14-11	D04311P	2			D08019P	5			ALL
	0117	22	G5		3-10	22-14-11	D08019P	22			TB1401Y	B015	1A		ALL
	0118	22	G5		1-10	22-18-11	D10137C	A05			TB1401Y	A019	1A		ALL
	0119	20	G5		3-9	22-18-11	D46011P	4			TB1401Y	A019	1A		ALL
	0120	22	G5		1-10	22-18-11	D10137C	B05			TB1401Y	A019	1A		ALL
	0121	22	G5		4-7	22-18-11	D10137C	J03			D41453P	2			ALL
	0122	22	G5		2-1	22-18-11	D10137C	D05			GD01401	AC..	1A		ALL
	0123	22	G5		2-1	22-18-11	D10137C	E05			GD01401	AC..	1A		ALL
	0124	20	G5		3-9	22-18-11	D10137C	53			D40047P	25			ALL
	0125	22	G5		3-9	22-18-11	D10137C	D01			D40047P	26			ALL
	0126	22	G5		3-9	22-18-11	D10137C	K01			D40047P	27			ALL
	0127	22	G5		3-9	22-18-11	D10137C	F03			D40047P	28			ALL
	0128	22	G5		3-9	22-18-11	D10137C	C03			D40047P	29			ALL
	0129	22	G5		3-9	22-18-11	D10137C	G03			D40047P	33			ALL
	0131	24	G6		4-3	22-11-75	D10137A	A07			D41463P	38			YD157-YR328
	0132	22	G5		3-10	22-11-11	D05971P	18			TB1402Z	A001	1A		ALL
	0133	22	G5		4-3	22-11-11	D05971P	19			GD01402	AC..	1A		ALL
	0134	22	G5		3-10	22-11-11	D05971P	14			TB1402Z	A001	1A		ALL
	0135	22	G5		4-3	22-11-11	D05971P	15			GD01402	AC..	1A		ALL
	0136	22	G5		3-10	22-11-11	D05971P	7			TB1402Z	A001	1A		ALL
	0137	22	G5		4-3	22-11-11	D05971P	8			GD01402	AC..	1A		ALL
	0138	22	G5		3-5	22-11-11	D04077P	18			TB1402Z	A001	1A		ALL
	0139	22	G5		3-9	22-11-11	D04077P	19			GD01402	AC..	1A		ALL
	0140	22	G5		3-9	22-11-11	D40047P	37			TB1402Z	A001	1A		ALL
	0141	20	G5		4-1	22-11-12	D08019P	24			TB1402Y	A013	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0140

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0141	286A0141				E1-4 SHELF - RIGHT (continued)										
0142	24		PK		1-10	34-31-21	D10721B	B05			TB1403Y	B005	1A		YC051-YD170
0143	24		PK		1-10	34-31-21	D10721B	J04			TB1403Y	B005	1A		ALL
0144	24		PK		1-10	34-31-21	D10721B	K04			TB1403Y	B005	1A		ALL
0146	22		G5		2-4	22-11-75	D10137A	B07			GD01401	DC..	1A		YC051-YL999, YR301-YR328
0152	22		PA		4-0	32-64-21	D40047P	1			D10137A	G03			ALL
0157	22		G5		2-7	23-15-15	D40496P	15			D04273P	8			YC051-YC052
0157	22		PA		2-7	23-15-15	D40496P	15			D04273P	8			YC053-YD157
0158	22		PA		4-5	23-15-15	D40496P	16			TB1404Y	A007	1A		YC053-YD157
0159	22		PA		0-7	23-15-15	TB1404Y	A005	1A		TB1404Y	B007	1A		YC053-YD157
0160	20		PA		2-7	23-71-01	D40496P	19			D04273P	12			ALL
0161	22		CQ		4-1	22-14-11	D10137B	J04			D08019P	10			YD157-YR328
0162	24		G6		5-0	31-62-41	D45123P	53			TB1404Y	A005	1A		YD158-YR328
0179	24		G6		5-0	22-11-75	D10137A	D14			D45517P	1			YD157-YR328
0180	24		G6		5-0	22-11-75	D10137A	E14			D45517P	2			YD157-YR328
0181	24		G6		5-0	22-11-75	D10137A	F14			D45517P	3			YD157-YR328
0182	24		G6		5-0	22-11-75	D10137A	F15			D45517P	5			YD157-YR328
0183	24		G6		5-0	22-11-75	D10137A	C13			D45517P	6			YD157-YR328
0186	24		G6		5-0	22-11-75	D10137A	E13			D45517P	7			YD157-YR328
0187	24		G6		4-11	22-11-75	D10137B	C13			D45517P	8			YD157-YR328
0188	24		G6		4-11	22-11-75	D10137B	F15			D45517P	9			YD157-YR328
0189	24		G6		4-11	22-11-75	D10137B	E13			D45517P	10			YD157-YR328
0190	24		G6		4-11	22-11-75	D10137B	G14			D45517P	11			YD157-YR328
0191	24		G6		4-9	22-11-75	D10137C	E01			D45517P	12			YD157-YR328
0192	24		G6		4-11	22-11-75	D10137B	E14			D45517P	13			YD157-YR328
0193	24		G6		4-11	22-11-75	D10137B	F14			D45517P	14			YD157-YR328
0194	24		G6		4-11	22-11-75	D10137B	C14			D45517P	15			YD157-YR328
0195	24		G6		4-2	22-11-75	D10137B	C15			D41463P	48			YD157-YR328
0196	24		G6		4-2	22-11-75	D10137B	D14			D41463P	49			YD157-YR328
0197	22		G5		4-1	22-13-11	D10137A	J09			D41129P	24			YD157-YR328
0198	18		CQ		3-11	22-11-11	D10137C	55			D46031P	10			YD157-YR328
0199	24		G6		3-5	22-11-75	D08019P	25			D41463P	51			YD157-YR328
0201	22		G5		2-6	22-31-11	D04311P	7			D41463P	36			ALL
0202	22		PA		3-5	22-31-51	D05971P	2			D41463P	4			ALL
0203	22		PA		3-5	22-31-51	D05971P	1			D41463P	2			ALL
0204	22		PA		2-6	22-31-51	D04311P	8			D41463P	5			ALL
0206	22		G5		2-4	34-16-11	D40826P	24			D41129P	25			ALL
0207	22		PA		4-3	34-16-21	D40826P	26			D41453P	13			ALL
0208	22		PA		2-7	34-21-15	D40556P	26			D41129P	49			ALL

WIRE LIST

D280A108

91-21-11

Section W0140

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0141		286A0141				E1-4 SHELF - RIGHT (continued)									
	0209	22	PA		2-7	34-21-15	D40556P	44			D41129P	50			ALL
	0210	22	PA		2-7	34-21-15	D40556P	45			D41129P	51			ALL
	0211	22	PA		2-7	34-21-15	D40556P	11			D41129P	52			ALL
	0212	22	PA		3-11	34-21-15	D10137A	G01			D40556P	16			ALL
	0213	22	PA		3-10	34-21-15	D10137B	G01			D40556P	6			ALL
	0214	22	PA		7-1	34-61-16	D04311P	10			D41453P	1			ALL
	0215	22	PA		6-6	34-21-21	D40490P	17			D41463P	43			ALL
	0218	16	PA		4-4	47-30-11	D40826P	10	16		D04077P	27	16		YL951-YR328
	0220	20	PA		4-5	47-30-11	D04077P	28			D40332P	3			YL951-YR328
	0221	20	PA		4-2	47-30-11	D40490P	21			D40332P	4			YN231
	0222	20	PA		4-2	47-30-11	D40490P	23			D40332P	5			YL951-YR328
	0223	20	PA		4-2	47-30-11	D40490P	22			D40332P	6			YL951-YR328
	0224	20	PA		2-2	47-30-11	D43016P	11			D40332P	7			YL951-YR328
	0225	20	PA		4-2	47-30-11	D40806P	30			D40332P	8			YL951-YR328
	0226	20	PA		4-2	47-30-11	D40806P	33			D40332P	9			YL951-YR328
	0227	16	CQ		2-2	47-30-11	D40806P	16	16		D40490P	20	16		YL951-YR328
	0228	20	CQ		5-5	47-30-11	D40490P	24			D04077P	25			YL951-YR328
	0229	20	CQ		4-5	47-30-11	D04077P	26			D40332P	1			YL951-YR328
	0231	20	G5		4-5	28-23-11	D40496P	6			D40490P	5			YL951-YR328
	0232	20	G5		4-5	28-23-11	D40496P	7			D40490P	12			YL951-YR328
	0301	18	CQ		2-5	24-11-11	D40556P	9	18		D40496P	11			ALL
	0306	24	PK		2-4	34-61-26	D41453P	39			D40806P	13			YC059-YR328
	0307	24	PK		2-4	34-61-26	D41453P	40			D40806P	14			YC059-YR328
	0308	24	PK		4-11	22-11-53	D10137A	A11			D41453P	41			YC059-YR328
	0309	24	PK		4-11	22-11-53	D10137A	B11			D41453P	44			YC059-YR328
	0310	24	PK		4-11	22-11-53	D10137A	C11			D41453P	45			YC059-YR328
	0311	24	PK		4-11	22-11-53	D10137A	C10			D41453P	46			YC059-YR328
	0354	22	CQ		4-4	49-62-11	D40560P	9			D40346P	14			ALL
	0401R	22	X5	LA	5-1	26-11-21	D40806P	28			TB1404Y	A001	1A		ALL
	0401Z			LA	0-0	26-11-21	D40806P	DED			TB1404Y	DED			ALL
	0402R	22	X5	LB	4-2	26-11-21	D40346P	42			TB1404Y	A001	1A		ALL
	0402Z			LB	0-0	26-11-21	D40346P	DED			TB1404Y	DED			ALL
	0403R	22	X5	LC	5-1	26-11-21	D40806P	32			TB1404Y	B001	1A		ALL
	0403Z			LC	0-0	26-11-21	D40806P	DED			TB1404Y	DED			ALL
	0404R	22	X5	LD	4-2	26-11-21	D40346P	23			TB1404Y	B001	1A		ALL
	0404Z			LD	0-0	26-11-21	D40346P	DED			TB1404Y	DED			ALL
	0405R	22	X5	LE	4-1	26-11-21	D40826P	22			TB1404Y	A001	1A		ALL
	0405Z			LE	0-0	26-11-21	D40826P	DED			TB1404Y	DED			ALL
	0406R	22	X5	LF	4-1	26-11-21	D40826P	21			TB1404Y	A003	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0140

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0141	286A0141				E1-4 SHELF - RIGHT (continued)											
0406Z				LF	0-0	26-11-21		D40826P		DED		TB1404Y		DED		ALL
0407R	22		X5	LG	4-2	26-11-21		D40346P		24		TB1404Y	A003	1A		ALL
0407Z				LG	0-0	26-11-21		D40346P		DED		TB1404Y		DED		ALL
0408R	22		X5	LH	4-1	26-11-21		D40826P		20		TB1404Y	B003	1A		ALL
0408Z				LH	0-0	26-11-21		D40826P		DED		TB1404Y		DED		ALL
0409R	22		X5	LI	4-2	26-11-21		D40346P		47		TB1404Y	B003	1A		ALL
0409Z				LI	0-0	26-11-21		D40346P		DED		TB1404Y		DED		ALL
0415R	22		PH		3-11	26-12-11		D00742		7		D46011P		11		ALL
0416R	20		PH		2-5	26-12-11		D00742		6		GD01404	DC..	1A		ALL
0417R	20		PH		2-5	26-12-11		D00742		5		GD01404	DC..	1A		ALL
0418R	20		X5	LJ	2-5	26-12-11		D00742		1		GD01404	AC..	1A		ALL
0418Z				LJ	0-0	26-12-11		D00742		DED		GD01404		DED		ALL
0419R	20		X5	LK	2-5	26-12-11		D00742		28		GD01404	AC..	1A		ALL
0419Z				LK	0-0	26-12-11		D00742		DED		GD01404		DED		ALL
0420R	22		X5	LL	5-2	26-12-11		D40806P		12		TB1404Y	B005	1A		ALL
0420Z				LL	0-0	26-12-11		D40806P		DED		TB1404Y		DED		ALL
0421R	22		X5	LM	2-8	26-12-11		D00742		3		TB1404Y	B005	1A		ALL
0421Z				LM	0-0	26-12-11		D00742		DED		TB1404Y		DED		ALL
0422R	20		X5	LN	3-7	26-12-11		D00742		21		D40346P		28		ALL
0422Z				LN	0-0	26-12-11		D00742		DED		D40346P		DED		ALL
0423R	20		X5	LO	3-7	26-12-11		D00742		24		D40346P		15		ALL
0423Z				LO	0-0	26-12-11		D00742		DED		D40346P		DED		ALL
0424R	22		X5	LP	3-7	26-12-11		D00742		14		D40346P		31		ALL
0424Z				LP	0-0	26-12-11		D00742		DED		D40346P		DED		ALL
0425R	22		X5	LQ	2-7	26-12-11		D00742		25		TB1404Y	B003	1A		ALL
0425Z				LQ	0-0	26-12-11		D00742		DED		TB1404Y		DED		ALL
0426R	22		X5	LR	2-7	26-12-11		D00742		16		TB1404Y	A003	1A		ALL
0426Z				LR	0-0	26-12-11		D00742		DED		TB1404Y		DED		ALL
0427R	22		X5	LS	2-7	26-12-11		D00742		20		TB1404Y	B001	1A		ALL
0427Z				LS	0-0	26-12-11		D00742		DED		TB1404Y		DED		ALL
0428R	22		X5	LT	2-7	26-12-11		D00742		15		TB1404Y	A001	1A		ALL
0428Z				LT	0-0	26-12-11		D00742		DED		TB1404Y		DED		ALL
0429R	20		X5	LU	3-8	26-12-11		D00742		9		D43016P		17		ALL
0429Z				LU	0-0	26-12-11		D00742		DED		D43016P		S/R		ALL
0430R	20		X5	LV	3-7	26-12-11		D00742		29		D40346P		40		ALL
0430Z				LV	0-0	26-12-11		D00742		DED		D40346P		DED		ALL
0431R	22		X5	LW	3-9	26-12-11		D00742		23		D40556P		29		ALL
0431Z				LW	0-0	26-12-11		D00742		DED		D40556P		DED		ALL
0432R	22		X5	LX	3-9	26-12-11		D00742		22		D40556P		30		ALL

WIRE LIST

D280A108

91-21-11

Section W0140

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To			Effectivity				
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type		Splice	Equip	Term	Type
W0141	286A0141			E1-4 SHELF - RIGHT (continued)											
0432Z				LX	0-0	26-12-11	D00742	DED			D40556P	DED			ALL
0433R	22	X5		LY	3-9	26-12-11	D00742	17			D40556P	47			ALL
0433Z				LY	0-0	26-12-11	D00742	DED			D40556P	DED			ALL
0434R	22	X5		LZ	3-9	26-12-11	D00742	18			D40556P	48			ALL
0434Z				LZ	0-0	26-12-11	D00742	DED			D40556P	DED			ALL
0435R	22	X5		MA	3-9	26-12-11	D00742	19			D40556P	49			ALL
0435Z				MA	0-0	26-12-11	D00742	DED			D40556P	DED			ALL
0436R	20	X5		MB	4-0	26-12-11	D00742	10			D41129P	21			ALL
0436Z				MB	0-0	26-12-11	D00742	DED			D41129P	DED			ALL
0437R	20	X5		MC	3-7	26-12-11	D00742	11			D40346P	29			ALL
0437Z				MC	0-0	26-12-11	D00742	DED			D40346P	DED			ALL
0438R	20	X5		MD	3-7	26-12-11	D00742	13			D40346P	48			ALL
0438Z				MD	0-0	26-12-11	D00742	DED			D40346P	DED			ALL
0439R	20	X5		ME	3-7	26-12-11	D00742	27			D40346P	43			ALL
0439Z				ME	0-0	26-12-11	D00742	DED			D40346P	DED			ALL
0440R	20	X5		MF	3-8	26-12-11	D00742	8			D43016P	18			ALL
0440Z				MF	0-0	26-12-11	D00742	DED			D43016P	S/R			ALL
0441R	20	X5		MG	3-8	26-12-11	D00742	2			D43016P	19			ALL
0441Z				MG	0-0	26-12-11	D00742	DED			D43016P	S/R			ALL
0442R	20	X5		MH	3-8	26-12-11	D00742	4			D43016P	20			ALL
0442Z				MH	0-0	26-12-11	D00742	DED			D43016P	S/R			ALL
0443R	20	X5		MI	4-0	26-12-11	D00742	12			D41129P	22			ALL
0443Z				MI	0-0	26-12-11	D00742	DED			D41129P	DED			ALL
0453	22	PA			2-8	30-11-11	D41129P	46			D40496P	10			ALL
0454	20	CQ			4-2	76-21-11	D40806P	40			D40346P	30			ALL
0462	20	PA			2-3	80-11-11	D40556P	10			D40346P	9			ALL
0463	24	PK			2-3	80-11-11	D40556P	24			D40346P	8			ALL
0464	22	PA			4-9	78-34-21	D10137A	J03			D40490P	9			ALL
0503	22	G5			3-10	27-62-11	D40496P	17			D10137B	J03			ALL
0504	22	G5			3-9	27-62-11	D40496P	18			TB1402Z	A009	1A		ALL
0505	20	X1	CC		4-3	29-11-11	D40806P	3			D43016P	15			ALL
0505Z			CC		0-0	29-11-11	D40806P	S/R			D43016P	S/R			ALL
0506	20	X1	CD		4-3	29-11-11	D40806P	4			D43016P	16			ALL
0506Z			CD		0-0	29-11-11	D40806P	S/R			D43016P	S/R			ALL
0511	24	Y1	CE		2-3	29-33-11	D40556P	2			D40346P	26			ALL
0511Z			CE		0-0	29-33-11	D40556P	DED			D40346P	S/R			ALL
0512	24	Y1	CF		4-2	29-33-11	D40806P	7			D40346P	27			ALL
0512Z			CF		0-0	29-33-11	D40806P	S/R			D40346P	S/R			ALL
0552	20	PA			1-9	34-53-21	D46011P	8			D40047P	12			ALL

WIRE LIST

D280A108

91-21-11

Section W0140

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0141	286A0141			E1-4 SHELF - RIGHT (continued)											
0553	22		PA		1-9	34-55-21	D46011P		9		D40047P		9		ALL
0601	24		PK		4-2	32-42-11	D40806P		1		D40346P		54		ALL
0602	24		PK		4-2	32-42-11	D40806P		2		D40346P		34		ALL
0603	24		PK		2-1	32-44-11	D40826P		3		D43016P		1		ALL
0604	24		PK		2-1	32-44-11	D40826P		4		D43016P		2		ALL
0605	24		PK		2-1	32-44-11	D40826P		5		D43016P		5		ALL
0606	24		PK		2-1	32-44-11	D40826P		2		D43016P		4		ALL
0607	24		PK		2-1	32-44-11	D40826P		1		D43016P		3		ALL
0611	24		G6		2-2	32-41-11	D40346P		25		D43016P		6		ALL
0612	22		PA		4-0	32-64-21	D10137A		C01		D40047P		39		ALL
0651	16		CQ		2-2	35-21-11	D40826P		27		D40496P		5		ALL
0652	16		CQ		2-2	35-21-11	D40826P		23		D40496P		4		ALL
0653	16		CQ		2-2	35-21-11	D40826P		19		D40496P		3		ALL
0654	16		CQ		2-2	35-21-11	D40826P		15		D40496P		2		ALL
0655	22		CQ		2-2	35-21-11	D40826P		14		D40496P		1		ALL
0656	22		CQ		2-5	35-21-11	D40556P		18		D40496P		12		ALL
0657	22		CQ		4-4	35-21-11	D40556P		19		D40806P		5		ALL
0658	22		CQ		2-2	35-11-11	D40806P		39		D40490P		14		ALL
0659	22		CQ		4-4	35-11-11	D40556P		12		D40490P		13		ALL
0702	22		PA		4-3	34-31-21	D10721C		9		D46011P		1		ALL
0703	20		PA		1-9	34-31-21	D10721C		7		GD01403	AC..	1A		ALL
0704	20		PA		1-9	34-31-21	D10721C		8		GD01403	ST..	1A		ALL
0706	22		PA		5-1	34-31-21	D10721B		A04		D40490P		7		ALL
0709	22		PA		4-7	34-51-21	D03625C		2		D46011P		2		ALL
0710	20		PA		1-11	34-51-21	D03625C		3		GD01403	AC..	1A		ALL
0711	20		PA		1-11	34-51-21	D03625C		4		GD01403	ST..	1A		ALL
0712	22		PA		3-6	34-51-21	D45123P		1		D46011P		3		ALL
0713	22		PA		2-1	34-51-21	D03625B		D02		GD01403	DC..	1A		ALL
0714	22		PA		5-5	34-51-21	D03625B		A15		D40490P		8		ALL
0715	22		CQ		4-1	34-51-41	D10137A		D01		D41129P		18		ALL
0716	22		CQ		2-7	34-51-41	D40556P		3		D41129P		20		ALL
0717	22		PA		4-2	34-51-41	D10137B		K14		D41463P		17		ALL
0718	22		PA		4-2	34-51-41	D10137B		E07		D41463P		16		ALL
0719	22		PA		4-2	34-51-41	D10137B		E03		D41463P		13		ALL
0720	22		PA		4-8	34-51-41	D41453P		12		TB1401Y	A021	1A		ALL
0721	22		PA		2-1	34-51-41	D10137B		A07		TB1401Y	A021	1A		ALL
0722	22		PA		2-1	34-51-41	D10137B		J07		TB1401Y	A021	1A		ALL
0723	22		PA		2-1	34-51-41	D10137B		J01		TB1401Y	B021	1A		ALL
0724	22		PA		2-2	34-51-41	D10137A		K12		TB1401Y	B021	1A		ALL

WIRE LIST

D280A108

91-21-11
Section W0140
Page 9
Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0141	286A0141				E1-4 SHELF - RIGHT (continued)											
0725	22		PA		4-4	34-51-41	D45123P		3			TB1401Y	B021	1A		ALL
0726	22		PA		4-0	34-51-41	D41463P		3			TB1401Y	B019	1A		YL951-YR328
0727	22		PA		2-0	34-51-41	D10137B		C02			TB1401Y	B019	1A		YL951-YR328
0728	22		PA		4-3	34-51-41	D45123P		15			TB1401Y	B019	1A		YL951-YR328
0729	22		PA		4-1	34-51-41	D41129P		19			D10137A	C02			YL951-YR328
0730	22		PA		1-11	34-31-21	D10721B		D05			GD01403	DC..	1A		YL951-YR328
0731	22		PA		1-11	34-31-21	D10721B		D07			GD01403	DC..	1A		YL951-YR328
0732	22		PA		1-11	34-31-21	D10721B		H05			GD01403	DC..	1A		YL951-YR328
0733	22		PA		1-11	34-31-21	D10721B		J05			GD01403	DC..	1A		YL951-YR328
0801	24		PK		4-2	31-31-15	D45143P		1			TB1401Y	B015	1A		ALL
0802R	22		PH		5-0	31-31-15	D45143P		2			TB1404Y	B005	1A		ALL
0851	20		CQ		4-11	31-52-11	D40826P		28			D41463P	1			ALL
0901	22		G5		2-4	23-22-11	D40826P		9			D04273P	7			YC051-YC052
0901	22		G5		4-1	23-22-11	D40826P		9			TB1404Y	A005	1A		YC053-YR328
0902	22		G5		4-6	23-22-11	TB1404Y		A005	1A		D04273P	7			YC053-YD170
0902	22		G5		4-6	23-22-11	D04273P		7			TB1404Y	A005	1A		YL951-YR328
1001	22		X1	ZA	2-3	78-32-51	D40346P		44			D40496P	8			ALL
1001Z				ZA	0-0	78-32-51	D40346P		S/R			D40496P	S/R			ALL
1002	22		X1	ZB	2-3	78-32-51	D40346P		45			D40496P	9			ALL
1002Z				ZB	0-0	78-32-51	D40346P		S/R			D40496P	S/R			ALL
1011	22		X1	ZN	3-11	22-11-11	D10137B		H11			D40047P	4			ALL
1011Z				ZN	0-0	22-11-11	GB01402		ST..	1A		D40047P	S/R			ALL
1012	22		X1	ZO	4-1	22-11-11	D10137A		H11			D41129P	1			ALL
1012Z				ZO	0-0	22-11-11	GB01401		ST..	1A		D41129P	S/R			ALL
1013	22		X1	ZH	4-9	22-11-81	D10137B		K09			D45553P	3			YD157-YD170, YN231-YN501
1013	22		X1	ZJ	4-9	22-11-81	D10137B		K09			D45553P	3			YL951-YL999, YR301-YR328
1013Z				ZH	0-0	22-11-81	GB01402		ST..	1A		D45553P	S/R			YD157-YD170, YN231-YN501
1013Z				ZJ	0-0	22-11-81	GB01402		ST..	1A		D45553P	S/R			YL951-YL999, YR301-YR328
1014	22		X1	ZI	4-10	22-11-81	D10137A		K09			D45553P	1			YD157-YR328
1014Z				ZI	0-0	22-11-81	GB01401		ST..	1A		D45553P	S/R			YD157-YR328
2001B	22		X2	AA	4-2	22-11-11	D10137A		H14			D08019P	2			ALL
2001R	22		X2	AA	0-0	22-11-11	D10137A		K14			D08019P	1			ALL
2001Z				AA	0-0	22-11-11	D10137A		PERG	1A		D08019P	S/R			YC051-YL953, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W0140

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0141	286A0141				E1-4 SHELF - RIGHT (continued)										
2001Z				AA	0-0	22-11-11	GB01402	ST..	1A		D08019P	S/R			YL954-YL999, YN236-YR328
2006B	22	X2	AF		4-0	22-11-31	D10137B	F11			D41129P	28			YC051-YD155
2006R	22	X2	AF		0-0	22-11-31	D10137B	G11			D41129P	27			YC051-YD155
2006Z			AF		0-0	22-11-31	GB01402	ST..	1A		D41129P	S/R			YC051-YD155
2007B	22	X2	AG		4-0	22-11-31	D10137A	F11			D40047P	11			YC051-YD155
2007R	22	X2	AG		0-0	22-11-31	D10137A	G11			D40047P	10			YC051-YD155
2007Z			AG		0-0	22-11-31	GB01402	ST..	1A		D40047P	S/R			YC051-YD155
2008B	22	X2	AH		4-1	22-11-31	D10137B	J06			D05971P	17			ALL
2008R	22	X2	AH		0-0	22-11-31	D10137B	K06			D05971P	16			ALL
2008Z			AH		0-0	22-11-31	GB01402	ST..	1A		D05971P	DED			ALL
2009B	22	X2	AI		3-7	22-11-31	D10137B	A12			D04077P	2			ALL
2009R	22	X2	AI		0-0	22-11-31	D10137B	B12			D04077P	1			ALL
2009Z			AI		0-0	22-11-31	GB01402	ST..	1A		D04077P	S/R			ALL
2010B	22	X2	AJ		1-10	22-11-31	D10137B	A15			TB1401Y	B011	1A		ALL
2010R	22	X2	AJ		0-0	22-11-31	D10137B	B15			TB1401Y	A011	1A		ALL
2010Z			AJ		0-0	22-11-31	GB01402	ST..	1A		GB01401	ST..	1A		ALL
2011B	22	X2	AK		3-7	22-11-31	D10137B	D12			D04077P	9			ALL
2011R	22	X2	AK		0-0	22-11-31	D10137B	E12			D04077P	8			ALL
2011Z			AK		0-0	22-11-31	GB01402	ST..	1A		D04077P	S/R			ALL
2012B	22	X2	AL		3-3	22-11-31	D04077P	5			TB1401Y	B011	1A		ALL
2012R	22	X2	AL		0-0	22-11-31	D04077P	4			TB1401Y	A011	1A		ALL
2012Z			AL		0-0	22-11-31	D04077P	S/R			GB01401	ST..	1A		ALL
2013B	22	X2	AM		3-3	22-11-31	D04077P	7			TB1401Y	B011	1A		ALL
2013R	22	X2	AM		0-0	22-11-31	D04077P	6			TB1401Y	A011	1A		ALL
2013Z			AM		0-0	22-11-31	D04077P	S/R			GB01401	ST..	1A		ALL
2014B	22	X2	AN		3-3	22-11-31	D04077P	15			TB1401Y	B011	1A		ALL
2014R	22	X2	AN		0-0	22-11-31	D04077P	14			TB1401Y	A011	1A		ALL
2014Z			AN		0-0	22-11-31	D04077P	S/R			GB01401	ST..	1A		ALL
2015B	22	X2	AO		3-7	22-11-31	D10137B	D15			D04077P	38			ALL
2015R	22	X2	AO		0-0	22-11-31	D10137B	E15			D04077P	37			ALL
2015Z			AO		0-0	22-11-31	GB01402	ST..	1A		D04077P	S/R			ALL
2016B	24	Y2	AP		3-11	22-11-51	D08019P	13			TB1402Z	B005	1A		ALL
2016R	24	Y2	AP		0-0	22-11-51	D08019P	12			TB1402Z	A005	1A		ALL
2016Z			AP		0-0	22-11-51	D08019P	S/R			GB01402	ST..	1A		ALL
2017B	24	Y2	AQ		3-10	22-11-51	D08019P	19			TB1401Y	B013	1A		ALL
2017R	24	Y2	AQ		0-0	22-11-51	D08019P	18			TB1401Y	A013	1A		ALL
2017Z			AQ		0-0	22-11-51	D08019P	S/R			GB01401	ST..	1A		ALL
2018B	24	Y2	AR		4-2	22-11-51	D45143P	19			TB1401Y	B013	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0140

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W0141	286A0141			E1-4 SHELF - RIGHT (continued)											
2018R	24	Y2	AR	0-0	22-11-51	D45143P	18			TB1401Y	A013	1A		ALL	
2018Z			AR	0-0	22-11-51	D45143P	S/R			GB01401	ST..	1A		ALL	
2019B	24	Y2	AS	4-2	22-11-51	D45143P	11			TB1401Y	B013	1A		ALL	
2019R	24	Y2	AS	0-0	22-11-51	D45143P	10			TB1401Y	A013	1A		ALL	
2019Z			AS	0-0	22-11-51	D45143P	S/R			GB01401	ST..	1A		ALL	
2020B	24	Y2	AT	4-3	22-11-51	D45143P	13			TB1402Z	B005	1A		ALL	
2020R	24	Y2	AT	0-0	22-11-51	D45143P	12			TB1402Z	A005	1A		ALL	
2020Z			AT	0-0	22-11-51	D45143P	S/R			GB01402	ST..	1A		ALL	
2021B	24	Y2	AU	4-3	22-11-51	D45143P	15			TB1402Z	B005	1A		ALL	
2021R	24	Y2	AU	0-0	22-11-51	D45143P	14			TB1402Z	A005	1A		ALL	
2021Z			AU	0-0	22-11-51	D45143P	S/R			GB01402	ST..	1A		ALL	
2022B	24	Y2	AV	4-3	22-11-51	D45143P	17			TB1402Z	B005	1A		ALL	
2022R	24	Y2	AV	0-0	22-11-51	D45143P	16			TB1402Z	A005	1A		ALL	
2022Z			AV	0-0	22-11-51	D45143P	S/R			GB01402	ST..	1A		ALL	
2023B	24	Y2	AW	1-10	22-11-51	D10137A	A06			TB1402Z	B005	1A		ALL	
2023R	24	Y2	AW	0-0	22-11-51	D10137A	B06			TB1402Z	A005	1A		ALL	
2023Z			AW	0-0	22-11-51	D10137A	DED			GB01402	ST..	1A		ALL	
2024B	24	Y2	AX	2-0	22-11-51	D10137A	J06			TB1401Y	B013	1A		ALL	
2024R	24	Y2	AX	0-0	22-11-51	D10137A	K06			TB1401Y	A013	1A		ALL	
2024Z			AX	0-0	22-11-51	D10137A	DED			GB01401	ST..	1A		ALL	
2025B	24	Y2	AY	4-0	22-11-51	D10137B	D10			D41129P	30			ALL	
2025R	24	Y2	AY	0-0	22-11-51	D10137B	E10			D41129P	29			ALL	
2025Z			AY	0-0	22-11-51	GB01402	ST..	1A		D41129P	S/R			ALL	
2026B	24	Y2	AZ	4-0	22-11-51	D10137B	A10			D41129P	43			ALL	
2026R	24	Y2	AZ	0-0	22-11-51	D10137B	B10			D41129P	42			ALL	
2026Z			AZ	0-0	22-11-51	GB01402	ST..	1A		D41129P	S/R			ALL	
2027B	24	Y2	BA	4-0	22-11-51	D10137A	D10			D40047P	17			ALL	
2027R	24	Y2	BA	0-0	22-11-51	D10137A	E10			D40047P	16			ALL	
2027Z			BA	0-0	22-11-51	GB01401	ST..	1A		D40047P	S/R			ALL	
2028B	24	Y2	BB	4-0	22-11-51	D10137A	A10			D40047P	14			ALL	
2028R	24	Y2	BB	0-0	22-11-51	D10137A	B10			D40047P	13			ALL	
2028Z			BB	0-0	22-11-51	GB01401	ST..	1A		D40047P	S/R			ALL	
2029B	22	M2	BC	4-0	22-12-31	D10137A	J11			D40047P	19			YC051-YD155	
2029R	22	M2	BC	0-0	22-12-31	D10137A	K11			D40047P	18			YC051-YD155	
2029ZI			BC	0-0	22-12-31	D10137A	DED			D40047P	20			YC051-YD155	
2029ZO			BC	0-0	22-12-31	GB01401	ST..	1A		D40047P	S/R			YC051-YD155	
2030B	22	M2	BD	4-0	22-12-41	D10137B	J11			D41129P	34			YC051-YD155	
2030R	22	M2	BD	0-0	22-12-41	D10137B	K11			D41129P	33			YC051-YD155	
2030ZI			BD	0-0	22-12-41	GB01402	ST..	1A		D41129P	35			YC051-YD155	

WIRE LIST

D280A108

91-21-11

Section W0140

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0141	286A0141				E1-4 SHELF - RIGHT (continued)										
2030ZO				BD	0-0	22-12-41	GB01401	ST..	1A		D41129P	S/R			YC051-YD155
2031B	22	PB	BE		4-2	22-12-41	D10137A	E01			D05971P	21			ALL
2031R	22	PB	BE		0-0	22-12-41	D10137A	E02			D05971P	20			ALL
2032B	22	PB	BF		4-1	22-12-41	D10137B	E01			D05971P	10			ALL
2032R	22	PB	BF		0-0	22-12-41	D10137B	E02			D05971P	9			ALL
2033B	22	X2	BG		4-3	22-12-41	D10137A	C12			D04081P	10			ALL
2033R	22	X2	BG		0-0	22-12-41	D10137A	D12			D04081P	9			ALL
2033Z			BG		0-0	22-12-41	GB01401	ST..	1A		D04081P	DED			ALL
2034B	22	X2	BH		4-3	22-12-41	D10137A	A15			D04081P	20			YC051-YD155
2034B	22	X2	BH		2-0	22-12-41	D10137A	A15			TB1402Y	B015	1A		YD157-YR328
2034R	22	X2	BH		0-0	22-12-41	D10137A	B15			D04081P	19			YC051-YD155
2034R	22	X2	BH		0-0	22-12-41	D10137A	B15			TB1402Y	A015	1A		YD157-YR328
2034Z			BH		0-0	22-12-41	GB01401	ST..	1A		D04081P	DED			YC051-YD155
2034Z			BH		0-0	22-12-41	GB01401	ST..	1A		GB01402	ST..	1A		YD157-YR328
2035B	22	X2	BI		4-3	22-12-41	D10137A	A12			D04081P	23			ALL
2035R	22	X2	BI		0-0	22-12-41	D10137A	A13			D04081P	22			ALL
2035Z			BI		0-0	22-12-41	GB01401	ST..	1A		D04081P	DED			ALL
2036B	22	X2	BJ		4-3	22-12-41	D10137A	D15			D04081P	8			ALL
2036R	22	X2	BJ		0-0	22-12-41	D10137A	E15			D04081P	7			ALL
2036Z			BJ		0-0	22-12-41	GB01401	ST..	1A		D04081P	DED			ALL
2037B	22	PB	BK		3-10	22-18-11	D10137C	D04			D41129P	37			ALL
2037R	22	PB	BK		0-0	22-18-11	D10137C	E04			D41129P	36			ALL
2038B	22	PB	BL		3-9	22-18-11	D10137C	A01			D40047P	31			ALL
2038R	22	PB	BL		0-0	22-18-11	D10137C	B01			D40047P	30			ALL
2039B	24	Y2	BM		4-3	27-32-22	D10137A	G04			D41463P	9			ALL
2039R	24	Y2	BM		0-0	27-32-22	D10137A	H04			D41463P	8			ALL
2039Z			BM		0-0	27-32-22	GB01402	ST..	1A		D41463P	S/R			ALL
2040B	24	Y2	CP		4-5	22-11-51	D10137B	A08			D45143P	23			ALL
2040R	24	Y2	CP		0-0	22-11-51	D10137B	B08			D45143P	22			ALL
2040Z			CP		0-0	22-11-51	D10137B	DED			D45143P	S/R			ALL
2041B	24	Y2	KF		1-10	34-58-21	D10721B	F09			TB1403Y	B007	1A		YC053-YR328
2041R	24	Y2	KF		0-0	34-58-21	D10721B	E09			TB1403Y	A007	1A		YC053-YR328
2041Z			KF		0-0	34-58-21	D10721B	PERG	1A		GB01403	ST..	1A		YC053-YR328
2043B	24	Y2	KG		4-4	34-58-21	D40047P				TB1403Y	B007	1A		YC053-YR328
2043R	24	Y2	KG		0-0	34-58-21	D40047P				TB1403Y	A007	1A		YC053-YR328
2043Z			KG		0-0	34-58-21	D40047P	S/R			GB01403	ST..	1A		YC053-YR328
2044B	24	Y2	KI		5-1	34-58-21	D04311P				TB1403Y	B007	1A		YC053-YR328
2044R	24	Y2	KI		0-0	34-58-21	D04311P				TB1403Y	A007	1A		YC053-YR328
2044Z			KI		0-0	34-58-21	D04311P	S/R			GB01403	ST..	1A		YC053-YR328

WIRE LIST

D280A108

91-21-11

Section W0140

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0141		286A0141				E1-4 SHELF - RIGHT (continued)										
2045B		24		Y2	KJ	4-2	31-62-21	D08019P		20		TB1402Y	B017	1A		YC051-YD157
2045R		24		Y2	KJ	0-0	31-62-21	D08019P		21		TB1402Y	A017	1A		YC051-YD157
2045Z					KJ	0-0	31-62-21	D08019P		S/R		GB01402	ST..	1A		YC051-YD157
2046B		24		Y2	KM	5-0	31-62-21	D40049P		4		TB1402Y	B017	1A		YC051-YD157
2046R		24		Y2	KM	0-0	31-62-21	D40049P		3		TB1402Y	A017	1A		YC051-YD157
2046Z					KM	0-0	31-62-21	D40049P		S/R		GB01402	ST..	1A		YC051-YD157
2048B		22		X2	KH	4-11	31-32-15	D41453P		38		TB1402Y	B023	1A		YC059-YR328
2048R		22		X2	KH	0-0	31-32-15	D41453P		37		TB1402Y	A023	1A		YC059-YR328
2048Z					KH	0-0	31-32-15	D41453P		S/R		GB01402	ST..	1A		YC059-YR328
2049B		22		X2	KT	2-1	31-32-15	D10137A		F06		TB1402Y	B023	1A		YC059-YR328
2049R		22		X2	KT	0-0	31-32-15	D10137A		G06		TB1402Y	A023	1A		YC059-YR328
2049Z					KT	0-0	31-32-15	D10137A		DED		GB01402	ST..	1A		YC059-YR328
2050B		22		X2	KK	4-7	31-32-15	D45143P		38		TB1402Y	B023	1A		YC059-YR328
2050R		22		X2	KK	0-0	31-32-15	D45143P		37		TB1402Y	A023	1A		YC059-YR328
2050Z					KK	0-0	31-32-15	D45143P		S/R		GB01402	ST..	1A		YC059-YR328
2051B		24		Y2	KL	4-11	22-11-53	D10137A		D06		D41453P		43		YC059-YR328
2051R		24		Y2	KL	0-0	22-11-53	D10137A		E06		D41453P		42		YC059-YR328
2051Z					KL	0-0	22-11-53	GB01402		ST..	1A	D41453P	S/R			YC059-YR328
2053B		22		X2	PA	4-9	22-11-81	D45553P		21		TB1402Y	B015	1A		YD157-YR328
2053R		22		X2	PA	0-0	22-11-81	D45553P		9		TB1402Y	A015	1A		YD157-YR328
2053Z					PA	0-0	22-11-81	D45553P		S/R		GB01402	ST..	1A		YD157-YR328
2054B		22		X2	PB	4-10	22-11-81	D10137A		G11		D45553P		15		YD157-YR328
2054R		22		X2	PB	0-0	22-11-81	D10137A		F11		D45553P		14		YD157-YR328
2054Z					PB	0-0	22-11-81	GB01401		ST..	1A	D45553P	S/R			YD157-YR328
2055B		22		X2	PC	4-9	22-11-81	D10137B		J10		D45553P		17		YD157-YR328
2055R		22		X2	PC	0-0	22-11-81	D10137B		K10		D45553P		16		YD157-YR328
2055Z					PC	0-0	22-11-81	GB01402		ST..	1A	D45553P	S/R			YD157-YR328
2056B		22		X2	PD	4-9	22-11-81	D10137B		H07		D45553P		19		YD157-YR328
2056R		22		X2	PD	0-0	22-11-81	D10137B		H06		D45553P		18		YD157-YR328
2056Z					PD	0-0	22-11-81	GB01402		ST..	1A	D45553P	S/R			YD157-YR328
2057B		24		Y2	PH	4-11	34-21-14	D10137A		J04		D41453P		52		YD157-YR328
2057R		24		Y2	PH	0-0	34-21-14	D10137A		K04		D41453P		51		YD157-YR328
2057Z					PH	0-0	34-21-14	GB01401		ST..	1A	D41453P	S/R			YD157-YR328
2058B		24		Y2	PG	4-0	34-33-11	D10137B		J11		D41129P		34		YD157-YR328
2058R		24		Y2	PG	0-0	34-33-11	D10137B		K11		D41129P		33		YD157-YR328
2058Z					PG	0-0	34-33-11	GB01402		ST..	1A	D41129P	S/R			YD157-YR328
2059B		22		X2	PF	4-2	22-12-41	D04081P		20		TB1402Y	B015	1A		YD157-YR328
2059R		22		X2	PF	0-0	22-12-41	D04081P		19		TB1402Y	A015	1A		YD157-YR328
2059Z					PF	0-0	22-12-41	D04081P		DED		GB01402	ST..	1A		YD157-YR328

WIRE LIST

D280A108

91-21-11

Section W0140

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0141	286A0141				E1-4 SHELF - RIGHT (continued)										
2060B	24	Y2	PJ		0-7	22-11-51	D10137B	F11			SM00012		W		YD157-YR328
2060R	24	Y2	PJ		0-0	22-11-51	D10137B	G11			SM00011		W		YD157-YR328
2060Z			PJ		0-0	22-11-51	GB01402	ST..	1A		SM00013		W		YD157-YR328
2061B	24	Y2	PK		3-11	22-11-51	D40047P	11			SM00012		W		YD157-YR328
2061R	24	Y2	PK		0-0	22-11-51	D40047P	10			SM00011		W		YD157-YR328
2061Z			PK		0-0	22-11-51	D40047P	S/R			SM00013		W		YD157-YR328
2062B	24	Y2	PI		4-11	22-11-51	D40049P	12			SM00012		W		YD157-YR328
2062R	24	Y2	PI		0-0	22-11-51	D40049P	11			SM00011		W		YD157-YR328
2062Z			PI		0-0	22-11-51	D40049P	S/R			SM00013		W		YD157-YR328
2063B	22	X2	DP		4-4	34-58-21	D40047P	52			TB1403Y	B007	1A		YD158-YR328
2063R	22	X2	DP		0-0	34-58-21	D40047P	51			TB1403Y	A007	1A		YD158-YR328
2063Z			DP		0-0	34-58-21	D40047P	S/R			GB01403	ST..	1A		YD158-YR328
2101B	24	Y2	DA		4-3	22-31-52	D10137A	A04			D41463P	7			ALL
2101R	24	Y2	DA		0-0	22-31-52	D10137A	B04			D41463P	6			ALL
2101Z			DA		0-0	22-31-52	D10137A	PERG	1A		D41463P	S/R			YC051-YL953, YN231-YN235
2101Z			DA		0-0	22-31-52	GB01402	ST..	1A		D41463P	S/R			YL954-YL999, YN236-YR328
2102B	24	Y2	DB		4-1	34-21-13	D10137A	K02			D41129P	32			ALL
2102R	24	Y2	DB		0-0	34-21-13	D10137A	K03			D41129P	31			ALL
2102Z			DB		0-0	34-21-13	D10137A	PERG	1A		D41129P	S/R			YC051-YL953, YN231-YN235
2102Z			DB		0-0	34-21-13	GB01402	ST..	1A		D41129P	S/R			YL954-YL999, YN236-YR328
2103B	24	Y2	DC		4-9	34-21-23	D10137B	K02			D41453P	15			ALL
2103R	24	Y2	DC		0-0	34-21-23	D10137B	K03			D41453P	14			ALL
2103Z			DC		0-0	34-21-23	D10137B	DED			D41453P	S/R			ALL
2104B	24	Y2	DD		4-9	34-21-24	D10137B	D04			D41453P	17			ALL
2104R	24	Y2	DD		0-0	34-21-24	D10137B	E04			D41453P	16			ALL
2104Z			DD		0-0	34-21-24	D10137B	PERG	1A		D41453P	S/R			YC051-YL953, YN231-YN235
2104Z			DD		0-0	34-21-24	GB01402	ST..	1A		D41453P	S/R			YL954-YL999, YN236-YR328
2105B	24	Y2	DE		4-3	34-61-14	D10137A	D04			D41463P	11			ALL
2105R	24	Y2	DE		0-0	34-61-14	D10137A	E04			D41463P	10			ALL
2105Z			DE		0-0	34-61-14	D10137A	DED			D41463P	S/R			ALL
2106B	24	Y2	DF		2-7	34-21-23	D40049P	2			D41453P	19			ALL
2106R	24	Y2	DF		0-0	34-21-23	D40049P	1			D41453P	18			ALL
2106Z			DF		0-0	34-21-23	D40049P	S/R			D41453P	S/R			ALL

WIRE LIST

D280A108

91-21-11

Section W0140

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0141		286A0141					E1-4 SHELF - RIGHT (continued)									
2126B		24		Y2	DG	4-6	34-61-15	D40556P			5	D41453P		34		YC051-YD170
2126R		24		Y2	DG	0-0	34-61-15	D40556P			4	D41453P		33		YC051-YD170
2126Z					DG	0-0	34-61-15	D40556P			14	D41453P		S/R		YC051-YD170
2151B		24		Y2	FA	4-5	34-33-21	D10137B			A04	D45123P		43		ALL
2151R		24		Y2	FA	0-0	34-33-21	D10137B			B04	D45123P		42		ALL
2151Z					FA	0-0	34-33-21	D10137B			DED	D45123P		S/R		ALL
2152B		24		Y2	FB	4-5	34-55-21	D10137B			G04	D45123P		41		ALL
2152R		24		Y2	FB	0-0	34-55-21	D10137B			H04	D45123P		40		ALL
2152Z					FB	0-0	34-55-21	GB01401			ST..	D45123P		S/R		ALL
2153B		24		Y2	FC	7-0	34-57-21	D40049P			8	D45123P		45		ALL
2153R		24		Y2	FC	0-0	34-57-21	D40049P			7	D45123P		44		ALL
2153Z					FC	0-0	34-57-21	D40049P			S/R	D45123P		S/R		ALL
2201B		24		Y2	GA	2-5	73-24-11	D40346P			20	D41129P		45		ALL
2201R		24		Y2	GA	0-0	73-24-11	D40346P			19	D41129P		44		ALL
2201Z					GA	0-0	73-24-11	D40346P			S/R	D41129P		S/R		ALL
2202B		24		Y2	GB	2-3	76-21-11	D40556P			22	D40346P		3		ALL
2202R		24		Y2	GB	0-0	76-21-11	D40556P			21	D40346P		4		ALL
2202Z					GB	0-0	76-21-11	D40556P			DED	D40346P		DED		ALL
2203B		24		Y2	GC	3-6	73-24-21	D45123P			17	D40047P		50		ALL
2203R		24		Y2	GC	0-0	73-24-21	D45123P			16	D40047P		49		ALL
2203Z					GC	0-0	73-24-21	D45123P			S/R	D40047P		S/R		ALL
2251B		24		Y2	HA	4-6	24-33-11	D40560P			14	D40496P		13		ALL
2251R		24		Y2	HA	0-0	24-33-11	D40560P			4	D40496P		14		ALL
2251Z					HA	0-0	24-33-11	D40560P			DED	D40496P		DED		ALL
2252B		24		Y2	HB	2-4	24-33-11	D40560P			15	D40490P		1		ALL
2252R		24		Y2	HB	0-0	24-33-11	D40560P			5	D40490P		3		ALL
2252Z					HB	0-0	24-33-11	D40560P			DED	D40490P		DED		ALL
2253B		24		Y2	HC	2-4	24-33-11	D40560P			16	D40490P		15		ALL
2253R		24		Y2	HC	0-0	24-33-11	D40560P			6	D40490P		16		ALL
2253Z					HC	0-0	24-33-11	D40560P			DED	D40490P		DED		ALL
2301B		24		Y2	IA	4-1	34-31-11	D10137A			G02	D41129P		41		ALL
2301R		24		Y2	IA	0-0	34-31-11	D10137A			H02	D41129P		40		ALL
2301Z					IA	0-0	34-31-11	GB01401			ST..	D41129P		S/R		ALL
2302B		24		M5	IB	4-5	34-31-21	D10721B			K10	D04273P		2		ALL
2302R		24		M5	IB	0-0	34-31-21	D10721B			J10	D04273P		1		ALL
2302ZI					IB	0-0	34-31-21	D10721B			DED	D04273P		3		ALL
2302ZO					IB	0-0	34-31-21	D10721B			PERG	D04273P		S/R		ALL
2303B		24		Y2	IC	4-10	34-31-21	D10721B			K01	D45143P		21		ALL
2303R		24		Y2	IC	0-0	34-31-21	D10721B			J01	D45143P		20		ALL

WIRE LIST

D280A108

91-21-11

Section W0140

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0141	286A0141				E1-4 SHELF - RIGHT (continued)										
2303Z				IC	0-0	34-31-21	D10721B	PERG	1A		D45143P	S/R			ALL
2304B	24	Y2		ID	2-3	34-31-21	D10137B	G02			TB1403Y	B001	1A		ALL
2304R	24	Y2		ID	0-0	34-31-21	D10137B	H02			TB1403Y	A001	1A		ALL
2304Z				ID	0-0	34-31-21	GB01402	ST..	1A		GB01403	ST..	1A		ALL
2305B	24	Y2		IE	4-4	34-31-21	D40047P			36	TB1403Y	B001	1A		ALL
2305R	24	Y2		IE	0-0	34-31-21	D40047P			35	TB1403Y	A001	1A		ALL
2305Z				IE	0-0	34-31-21	D40047P	S/R			GB01403	ST..	1A		ALL
2306B	24	Y2		IF	1-9	34-31-21	D10721B	B01			TB1403Y	B001	1A		ALL
2306R	24	Y2		IF	0-0	34-31-21	D10721B	A01			TB1403Y	A001	1A		ALL
2306Z				IF	0-0	34-31-21	D10721B	PERG	1A		GB01403	ST..	1A		ALL
2307B	24	Y2		IG	1-11	34-31-21	D10721B	H01			TB1403Z	B009	1A		ALL
2307R	24	Y2		IG	0-0	34-31-21	D10721B	G01			TB1403Z	A009	1A		ALL
2307Z				IG	0-0	34-31-21	D10721B	PERG	1A		GB01403	ST..	1A		ALL
2308B	24	Y2		IH	4-5	34-31-21	D40047P			43	TB1403Z	B009	1A		YC051-YC052, YC065-YR328
2308R	24	Y2		IH	0-0	34-31-21	D40047P			42	TB1403Z	A009	1A		YC051-YC052, YC065-YR328
2308Z				IH	0-0	34-31-21	D40047P	S/R			GB01403	ST..	1A		YC051-YC052, YC065-YR328
2309B	24	Y2		II	4-11	34-31-21	D45123P			21	TB1403Z	B009	1A		ALL
2309R	24	Y2		II	0-0	34-31-21	D45123P			20	TB1403Z	A009	1A		ALL
2309Z				II	0-0	34-31-21	D45123P	S/R			GB01403	ST..	1A		ALL
2310B	24	Y2		IJ	4-11	34-31-21	D45123P			25	TB1403Z	B009	1A		ALL
2310R	24	Y2		IJ	0-0	34-31-21	D45123P			24	TB1403Z	A009	1A		ALL
2310Z				IJ	0-0	34-31-21	D45123P	S/R			GB01403	ST..	1A		ALL
2311B	24	Y2		IK	5-3	34-31-21	D41453P			4	TB1403Z	B009	1A		ALL
2311R	24	Y2		IK	0-0	34-31-21	D41453P			3	TB1403Z	A009	1A		ALL
2311Z				IK	0-0	34-31-21	D41453P	S/R			GB01403	ST..	1A		ALL
2312B	24	Y2		IL	5-3	34-31-21	D41453P			6	TB1403Z	B009	1A		ALL
2312R	24	Y2		IL	0-0	34-31-21	D41453P			5	TB1403Z	A009	1A		ALL
2312Z				IL	0-0	34-31-21	D41453P	S/R			GB01403	ST..	1A		ALL
2313B	24	Y2		IM	5-3	34-31-21	D41453P			55	TB1403Z	B009	1A		YL951-YR328
2313R	24	Y2		IM	0-0	34-31-21	D41453P			53	TB1403Z	A009	1A		YL951-YR328
2313Z				IM	0-0	34-31-21	D41453P	S/R			GB01403	ST..	1A		YL951-YR328
2314B	24	Y2		IN	4-10	34-51-21	D45123P			27	TB1403Y	B003	1A		ALL
2314R	24	Y2		IN	0-0	34-51-21	D45123P			26	TB1403Y	A003	1A		ALL
2314Z				IN	0-0	34-51-21	D45123P	S/R			GB01403	ST..	1A		ALL
2315B	24	Y2		IP	1-7	34-51-21	D03625B	C11			TB1403Y	B003	1A		ALL
2315R	24	Y2		IP	0-0	34-51-21	D03625B	B11			TB1403Y	A003	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0140

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W0141	286A0141	E1-4 SHELF - RIGHT (continued)													
2315Z			IP	0-0	34-51-21	D03625B	DED		GB01403	ST..	1A		ALL		
2316B	24	Y2	IQ	4-10	34-51-21	D45123P	55		TB1403Y	B003	1A		ALL		
2316R	24	Y2	IQ	0-0	34-51-21	D45123P	54		TB1403Y	A003	1A		ALL		
2316Z			IQ	0-0	34-51-21	D45123P	S/R		GB01403	ST..	1A		ALL		
2317B	24	M5	IR	4-9	34-51-21	D03625B	C07		D04273P	5			ALL		
2317R	24	M5	IR	0-0	34-51-21	D03625B	B07		D04273P	4			ALL		
2317ZI			IR	0-0	34-51-21	D03625B	DED		D04273P	6			ALL		
2317ZO			IR	0-0	34-51-21	D03625B	PERG	1A	D04273P	S/R			YC051-YL953, YN231-YN235 YL954-YL999, YN236-YR328		
2317ZO			IR	0-0	34-51-21	GB01404	ST..	1A	D04273P	S/R					
2318B	24	Y2	IS	2-8	34-51-21	D10137B	G08		D03625B	B04			ALL		
2318R	24	Y2	IS	0-0	34-51-21	D10137B	H08		D03625B	A04			ALL		
2318Z			IS	0-0	34-51-21	GB01402	ST..	1A	GB01403	ST..	1A		ALL		
2319B	24	Y2	IT	1-10	34-51-21	D03625B	C13		TB1403Z	B013	1A		ALL		
2319R	24	Y2	IT	0-0	34-51-21	D03625B	B13		TB1403Z	A013	1A		ALL		
2319Z			IT	0-0	34-51-21	D03625B	DED		GB01403	ST..	1A		ALL		
2320B	24	Y2	IU	6-0	34-51-21	D40049P	10		TB1403Z	B013	1A		ALL		
2320R	24	Y2	IU	0-0	34-51-21	D40049P	9		TB1403Z	A013	1A		ALL		
2320Z			IU	0-0	34-51-21	D40049P	S/R		GB01403	ST..	1A		ALL		
2321B	24	Y2	IV	5-0	34-51-21	D45123P	29		TB1403Z	B013	1A		ALL		
2321R	24	Y2	IV	0-0	34-51-21	D45123P	28		TB1403Z	A013	1A		ALL		
2321Z			IV	0-0	34-51-21	D45123P	S/R		GB01403	ST..	1A		ALL		
2322B	24	Y2	IW	5-0	34-51-21	D45123P	31		TB1403Z	B013	1A		ALL		
2322R	24	Y2	IW	0-0	34-51-21	D45123P	30		TB1403Z	A013	1A		ALL		
2322Z			IW	0-0	34-51-21	D45123P	S/R		GB01403	ST..	1A		ALL		
2323B	24	Y2	IX	5-0	34-51-21	D45123P	33		TB1403Z	B013	1A		ALL		
2323R	24	Y2	IX	0-0	34-51-21	D45123P	32		TB1403Z	A013	1A		ALL		
2323Z			IX	0-0	34-51-21	D45123P	S/R		GB01403	ST..	1A		ALL		
2324B	24	Y2	IY	5-5	34-51-21	D41453P	8		TB1403Z	B013	1A		ALL		
2324R	24	Y2	IY	0-0	34-51-21	D41453P	7		TB1403Z	A013	1A		ALL		
2324Z			IY	0-0	34-51-21	D41453P	S/R		GB01403	ST..	1A		ALL		
2325B	24	Y2	IZ	5-5	34-51-21	D41453P	10		TB1403Z	B013	1A		ALL		
2325R	24	Y2	IZ	0-0	34-51-21	D41453P	9		TB1403Z	A013	1A		ALL		
2325Z			IZ	0-0	34-51-21	D41453P	S/R		GB01403	ST..	1A		ALL		
2361B	24	Y2	KA	2-8	31-62-22	D04311P	14		D45123P	35			ALL		
2361R	24	Y2	KA	0-0	31-62-22	D04311P	13		D45123P	34			ALL		
2361Z			KA	0-0	31-62-22	D04311P	S/R		D45123P	S/R			ALL		
2362B	24	Y2	KB	4-1	31-62-15	D10137A	A02		D41129P	39			ALL		

WIRE LIST

D280A108

91-21-11

Section W0140

Page 18

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0141	286A0141				E1-4 SHELF - RIGHT (continued)										
2362R	24	Y2	KB		0-0	31-62-15	D10137A	B02			D41129P	38			ALL
2362Z			KB		0-0	31-62-15	GB01401	ST..	1A		D41129P	S/R			ALL
2363B	24	Y2	KC		4-5	31-62-25	D10137B	A02			D45123P	39			ALL
2363R	24	Y2	KC		0-0	31-62-25	D10137B	B02			D45123P	38			ALL
2363Z			KC		0-0	31-62-25	GB01402	ST..	1A		D45123P	S/R			ALL
2364B	24	Y2	KD		4-8	31-62-21	D04311P	18			TB1402Y	B017	1A		YC051-YD157
2364B	24	Y2	KD		3-10	31-62-21	D04311P	18			D08019P	20			YD158-YR328
2364R	24	Y2	KD		0-0	31-62-21	D04311P	17			TB1402Y	A017	1A		YC051-YD157
2364R	24	Y2	KD		0-0	31-62-21	D04311P	17			D08019P	21			YD158-YR328
2364Z			KD		0-0	31-62-21	D04311P	S/R			GB01402	ST..	1A		YC051-YD157
2364Z			KD		0-0	31-62-21	D04311P	S/R			D08019P	S/R			YD158-YR328
2501B	24	Y2	NA		5-3	34-58-21	D41453P	26			D10721B	D02			YC051-YC052
2501B	24	Y2	NA		5-3	34-58-21	D10721B	D02			D41453P	26			YC053-YR328
2501R	24	Y2	NA		0-0	34-58-21	D41453P	25			D10721B	C02			YC051-YC052
2501R	24	Y2	NA		0-0	34-58-21	D10721B	C02			D41453P	25			YC053-YR328
2501Z			NA		0-0	34-58-21	D41453P	S/R			D10721B	PERG	1A		YC051-YC052
2501Z			NA		0-0	34-58-21	D10721B	PERG	1A		D41453P	S/R			YC053-YR328
2502B	24	Y2	NB		5-3	34-58-21	D41453P	28			D10721B	B08			ALL
2502R	24	Y2	NB		0-0	34-58-21	D41453P	27			D10721B	A08			ALL
2502Z			NB		0-0	34-58-21	D41453P	S/R			D10721B	PERG	1A		ALL
2503B	24	Y2	NC		5-3	34-58-21	D41453P	30			D10721B	K02			YC051-YC052
2503B	24	Y2	NC		5-3	34-58-21	D10721B	K02			D41453P	30			YC053-YR328
2503R	24	Y2	NC		0-0	34-58-21	D41453P	29			D10721B	J02			YC051-YC052
2503R	24	Y2	NC		0-0	34-58-21	D10721B	J02			D41453P	29			YC053-YR328
2503Z			NC		0-0	34-58-21	D41453P	S/R			D10721B	PERG	1A		YC051-YC052
2503Z			NC		0-0	34-58-21	D10721B	PERG	1A		D41453P	S/R			YC053-YR328
2504B	24	Y2	ND		5-3	34-58-21	D41453P	32			D10721B	H08			YC051-YD158
2504R	24	Y2	ND		0-0	34-58-21	D41453P	31			D10721B	G08			YC051-YD158
2504Z			ND		0-0	34-58-21	D41453P	S/R			D10721B	PERG	1A		YC051-YD158
3001B	22	X3	XA		3-7	22-11-31	D10137B	J13			D04077P	12			ALL
3001R	22	X3	XA		0-0	22-11-31	D10137B	K13			D04077P	11			ALL
3001Y	22	X3	XA		0-0	22-11-31	D10137B	H13			D04077P	13			ALL
3001Z			XA		0-0	22-11-31	GB01402	ST..	1A		D04077P	S/R			ALL
3002B	22	X3	XB		3-7	22-11-31	D10137B	G15			D04077P	33			ALL
3002R	22	X3	XB		0-0	22-11-31	D10137B	J15			D04077P	32			ALL
3002Y	22	X3	XB		0-0	22-11-31	D10137B	H15			D04077P	34			ALL
3002Z			XB		0-0	22-11-31	GB01402	ST..	1A		D04077P	S/R			ALL
3003B	22	X3	XC		3-7	22-12-41	D10137B	F06			D04077P	23			ALL
3003R	22	X3	XC		0-0	22-12-41	D10137B	G06			D04077P	22			ALL

WIRE LIST

D280A108

91-21-11

Section W0140

Page 19

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0141		286A0141			E1-4 SHELF - RIGHT (continued)											
3003Y		22		X3	XC	0-0	22-12-41	D10137B	E06			D04077P	24			ALL
3003Z					XC	0-0	22-12-41	GB01402	ST..	1A		D04077P	S/R			ALL
3004B		22		X3	XD	4-3	22-12-41	D10137A	J13			D04081P	17			ALL
3004R		22		X3	XD	0-0	22-12-41	D10137A	K13			D04081P	16			ALL
3004Y		22		X3	XD	0-0	22-12-41	D10137A	H13			D04081P	18			ALL
3004Z					XD	0-0	22-12-41	GB01401	ST..	1A		D04081P	DED			ALL
3005B		22		X3	XE	4-3	22-12-41	D10137A	G15			D04081P	13			ALL
3005R		22		X3	XE	0-0	22-12-41	D10137A	J15			D04081P	12			ALL
3005Y		22		X3	XE	0-0	22-12-41	D10137A	H15			D04081P	14			ALL
3005Z					XE	0-0	22-12-41	GB01401	ST..	1A		D04081P	DED			ALL
3006B		22		X3	XI	4-10	22-11-81	D10137A	G09			D45553P	23			YD157-YR328
3006R		22		X3	XI	0-0	22-11-81	D10137A	H09			D45553P	22			YD157-YR328
3006Y		22		X3	XI	0-0	22-11-81	D10137A	G10			D45553P	24			YD157-YR328
3006Z					XI	0-0	22-11-81	GB01401	ST..	1A		D45553P	S/R			YD157-YR328
W0142		286A0142			FWD ENTRY LIGHT PANEL											
0001		20		PA		2-3	33-29-11	D40020J	1			D10756	1			YC051-YN260
0002		20		PA		2-3	33-29-11	D40020J	2			D10756	2			YC051-YN260
0003		20		PA		4-7	33-51-12	D03160	7			D40020J	3			YC051-YN260
0003		20		PA		9-4	33-51-12	D03160	7			D41082J	3			YN501-YR328
0004		20		PA		4-7	33-51-12	D03160	8			D40020J	4			YC051-YN260
0004		20		PA		9-4	33-51-12	D03160	8			D41082J	4			YN501-YR328
0005		20		PA		2-3	33-29-11	D40020J	5			D10756	5			YC051-YN260
0005		24		PK		8-11	33-29-11	D41082J	5			D14774	A			YN501-YR328
0006		20		PA		2-3	33-29-11	D40020J	6			D10756	6			YC051-YN260
0006		24		PK		8-11	33-29-11	D41082J	6			D14774	B			YN501-YR328
0007		20		PA		2-3	33-29-11	D40020J	7			D10756	7			YC051-YN260
0008		22		PA		2-3	33-29-11	D40020J	8			D10756	8			YC051-YN260
0009		22		PA		4-7	23-42-11	D40020J	9			D03160	4			YC051-YN260
0009		22		PA		9-4	23-42-11	D41082J	9			D03160	4			YN501-YR328
0010		22		PA		4-7	23-42-11	D40020J	10			D03160	6			YC051-YN260
0010		22		PA		9-4	23-42-11	D41082J	10			D03160	6			YN501-YR328
0011		22		PA		4-7	33-27-11	D40020J	11			D03160	3			YC051-YN260
0011		22		PA		9-4	33-27-11	D41082J	11			D03160	3			YN501-YR328
0012		22		PA		4-7	33-27-11	D40020J	12			D03160	2			YC051-YN260
0012		22		PA		9-4	33-27-11	D41082J	12			D03160	2			YN501-YR328
0013		22		PA		2-3	33-29-11	D40020J	13			D10756	3			YC051-YN260
0014		20		PA		2-3	33-29-11	D40020J	14			D10756	4			YC051-YN260
0015		20		PA		2-3	33-26-11	D40020J	15			SM00022		S		YC051-YC070

WIRE LIST

D280A108

91-21-11

Section W0140

Page 20

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0142	286A0142				FWD ENTRY LIGHT PANEL (continued)										
0015	20		PA		3-1	33-26-11	D40020J	15			L01301	=G	I		YD151-YN260
0015	20		PA		7-3	33-26-11	D41082J	15			L01301	=G	I		YN501-YR328
0016	22		PA		2-3	33-26-11	D40020J	16			SM00021		S		YC051-YC070
0016	22		PA		3-1	33-26-11	D40020J	16			L01301	=P	I		YD151-YN260
0016	22		PA		7-3	33-26-11	D41082J	16			L01301	=P	I		YN501-YR328
0017	22		PA		4-7	SPARE	D40020J	17			D03160		5		YC051-YN260
0017	22		PA		9-4	SPARE	D41082J	17			D03160		5		YN501-YR328
0018	22		PA		4-7	SPARE	D40020J	18			D03160		1		YC051-YN260
0018	22		PA		9-4	SPARE	D41082J	18			D03160		1		YN501-YR328
0021	22		PA		1-8	33-26-11	SM00021		S		L01329	CAP	Y		YC051-YC070
0022	22		PA		2-1	33-26-11	SM00021		S		L01301	=P	I		YC051-YC070
0023	20		PA		2-1	33-26-11	SM00022		S		L01301	=G	I		YC051-YC070
0024	20		PA		1-8	33-26-11	SM00022		S		L01329	CAP	Y		YC051-YC070
W0144	286A0144				FWD RECESSED LIGHT PANEL										
0001	18		PA		2-2	33-22-31	D11372	1			SM00001		S		YC051-YN260
0001	20		PA		3-9	33-26-31	D41088J	1			L01146	=P	Z		YN501-YR328
0002	18		PA		2-2	33-22-31	D11372	2			SM00002		S		YC051-YN260
0002	20		PA		3-9	33-26-31	D41088J	2			L01146	=G	Z3		YN501-YR328
0003	18		PA		2-2	33-22-31	D11372	3			SM00003		S		YC051-YN260
0005	24		PK		2-2	33-22-31	D11372	5			SM00005		S		YC051-YN260
0006	24		PK		2-2	33-22-31	D11372	6			SM00006		S		YC051-YN260
0007	20		PA		3-11	33-26-31	D40018J	7			D11356		1		YC051-YN260
0008	20		PA		3-11	33-26-31	D40018J	8			D11356		2		YC051-YN260
0009	20		PA		3-11	33-26-31	D40018J	9			D11356		3		YC051-YN260
0011	18		PA		7-5	33-22-31	D11384	1			SM00001		S		YC051-YN260
0012	18		PA		7-5	33-22-31	D11384	2			SM00002		S		YC051-YN260
0013	18		PA		7-5	33-22-31	D11384	3			SM00003		S		YC051-YN260
0015	24		PK		7-5	33-22-31	D11384	5			SM00005		S		YC051-YN260
0016	24		PK		7-5	33-22-31	D11384	6			SM00006		S		YC051-YN260
0021	18		PA		1-0	33-22-31	D40018J	1			SM00001		S		YC051-YN260
0022	18		PA		1-0	33-22-31	D40018J	2			SM00002		S		YC051-YN260
0023	18		PA		1-0	33-22-31	D40018J	3			SM00003		S		YC051-YN260
0025	24		PK		1-0	33-22-31	D40018J	5			SM00005		S		YC051-YN260
0026	24		PK		1-0	33-22-31	D40018J	6			SM00006		S		YC051-YN260
0040	20		PA		6-2	33-51-12	D40018J	10			L01417		1	C	YL951-YN260
0041	20		PA		6-2	33-51-12	D40018J	11			L01417		2	C	YL951-YN260

WIRE LIST

D280A108

91-21-11

Section W0140

Page 21

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				Effectivity
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W0145	286A0145				CAPT CONTROL SHAKER											
0001	20		PA		3-0	27-32-11		D00281	A			SP00089		S		YC051-YN236, YN501-YR317
0001	20		PA		2-8	27-32-11		D00281	A			SP00089		S		YN237-YN260, YR318-YR328
0002	20		PA		3-0	27-32-11		D00281	B			GD00041	DC..	E		YC051-YN236, YN501-YR317
0002	20		PA		2-11	27-32-11		D00281	B			GD00041	DC..	E		YN237-YN260, YR318-YR328
W0147	286A0147				F/O CONTROL SHAKER											
0001	20		PA		3-0	27-32-21		D00367	A			SP00091		S		YC051-YN236, YN501-YR317
0001	20		PA		2-10	27-32-21		D00367	A			SP00091		S		YN237-YN260, YR318-YR328
0002	20		PA		3-0	27-32-21		D00367	B			GD00053	DC..	E		YC051-YN236, YN501-YR317
0002	20		PA		2-7	27-32-21		D00367	B			GD00053	DC..	E		YN237-YN260, YR318-YR328

WIRE LIST

D280A108

91-21-11

Section W0140

Page 22 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0151	286A0151				E1-5 SHELF										
0001	20		PA		1-6	34-53-21	D00155C		1		TB1504Y	A001	1A		ALL
0002	20		PA		2-7	34-53-21	D41507P		32		TB1504Y	A001	1A		ALL
0003	20		PA		2-5	34-53-21	D41517P		3		TB1504Y	A001	1A		ALL
0004	20		PA		1-5	34-53-21	D00155C		7		GD01503	AC..	1A		ALL
0006	20		PA		1-5	34-53-21	D00155C		11		GD01503	ST..	1A		ALL
0007	24		PK		2-11	34-53-21	D41517P		7		D00155A	G07			YC051-YD157
0007	24		PK		2-10	34-53-21	D41517P		7		D00155A	G07			YD158-YR328
0008	20		PA		1-5	34-53-21	D00155C		8		GD01503	DC..	1A		ALL
0009	20		PA		2-6	34-53-21	D41517P		9		GD01503	ST..	1A		ALL
0010	20		PA		2-6	34-53-21	D41517P		10		GD01503	ST..	1A		ALL
0011	24		PK		2-11	34-53-21	D41517P		11		D00155A	K05			YC051-YD157
0011	24		PK		2-10	34-53-21	D41517P		11		D00155A	K05			YD158-YR328
0012	24		PK		2-11	34-53-21	D41517P		12		D00155A	B03			YC051-YD157
0012	24		PK		2-10	34-53-21	D41517P		12		D00155A	B03			YD158-YR328
0015	24		PK		2-11	34-53-21	D41517P		15		D00155A	J05			YC051-YD157
0015	24		PK		2-10	34-53-21	D41517P		15		D00155A	J05			YD158-YR328
0016	24		PK		2-10	34-53-21	D41517P		6		D00155B	E06			YC051-YD157
0016	24		PK		2-9	34-53-21	D41517P		6		D00155B	E06			YD158-YR328
0017	24		PK		0-7	34-53-21	D00155A	G03			D00155A	J03			ALL
0018	22		PA		1-4	34-55-21	D00169C		11		GD01502	ST..	1A		ALL
0019	22		PA		1-4	34-55-21	D00169C		7		GD01502	AC..	1A		ALL
001CO				BA	0-0	34-53-31	D00155A	= C71			D02705	= C1			ALL
001CX			OG	BA	2-7	34-53-31	D00155A	71			D02705	= A1			ALL
0020	24		PK		2-10	34-53-21	D41517P		1		D00155B	K03			YC051-YD157
0020	24		PK		2-9	34-53-21	D41517P		1		D00155B	K03			YD158-YR328
0021	22		PA		3-2	34-55-21	D00169C		1		D41507P	31			ALL
0022	24		PK		3-5	34-55-21	D00169B	B05			D04031P	6			ALL
0025	22		G5		2-8	23-12-21	D04125P		9		D00201B	D05			YD158-YD170
0025	22		PA		2-8	23-12-21	D00201B		D05		D04125P	9			YL951-YN260, YR301-YR328
0025	22		PA		2-8	23-12-21	D04125P		9		D00201B	D05			YN501
0026	22		PA		3-5	34-55-21	D00169B	K05			D04031P	13			ALL
0028	22		PA		3-0	34-55-21	D04031P		3		GD01502	DC..	1A		ALL
0029	22		PA		1-7	34-55-21	D00169B	A05			GD01502	ST..	1A		ALL
002CO				BB	0-0	34-53-31	D00155C	= C12			D02853	= C1			ALL
002CX			OF	BB	0-8	34-53-31	D00155C	12	DN		D02853	= A1			ALL
0031	16		PA		2-5	23-12-21	D41557P		21		TB1504W	A005	1		YC051-YD157
0031	16		PA		2-3	23-12-21	D41557P		21		D00201C	2			YD158-YR328
0032	16		PA		2-5	23-12-21	D41557P		23		TB1504W	A005	1		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0150

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0151		286A0151				E1-5 SHELF (continued)										
0033		16		PA		1-8	23-12-21	D00201C		2		TB1504W	A005	1		YC051-YD157
0034		18		PA		2-8	23-12-21	D04125P		7		TB1504W	A005	1		YC051-YD157
0035		16		PA		2-1	23-12-21	D00201C		4		GD01501	DC..	1		ALL
0036		22		PA		2-0	23-12-21	D00201B		D03		GD01503	DC..	1A		ALL
0037		22		PA		2-0	23-12-21	D00201B		A02		GD01503	DC..	1A		ALL
0038		22		PA		2-3	34-51-41	D04031P		38		D41557P		3		ALL
0039		24		PK		2-3	23-12-21	D00201B		B14		D04197P		7		ALL
003CO					BC	0-0	34-53-31	D02851		=C1		D41511P		=C1		ALL
003CX				OF	BC	1-9	34-53-31	D02851		=A1		D41511P		=A1		ALL
0040		22		PA		2-3	34-51-41	D04031P		12		D41557P		12		ALL
0041		22		PA		2-9	34-51-21	D04031P		54		D45125P		1		ALL
0043		22		PA		2-9	34-51-41	D04031P		31		D45125P		3		ALL
0044		22		PA		2-9	34-51-41	D04031P		51		D45125P		4		YC051-YD158
0044		22		PA		2-8	34-51-41	D04031P		51		TB1504W	B005	1		YL951-YR328
0048		22		PA		1-6	34-53-21	D00155B		G05		GD01503	DC..	%A		YD158-YR328
0049		22		PA		2-3	23-12-21	D04197P		8		D00201B		C01		ALL
004CO					BD	0-0	34-53-31	D00155B		=C71		D02711		=C1		ALL
004CX				OF	BD	2-4	34-53-31	D00155B		71		D02711		=A1		ALL
0052		24		PK		2-2	31-31-17	D45125P		14		D00201B		D01		ALL
0053		18		PA		2-8	23-12-21	D04125P		10		TB1504W	A005	1		YC051-YD157
0054		22		PA		2-8	23-12-21	D04125P		4		D00201B		D05		YC051-YD157
0055		22		G5		2-9	22-11-18	D04031P		5		D45125P		10		ALL
005CO					BE	0-0	34-55-21	D00169C		=C12		D02849		=C1		ALL
005CX				OF	BE	0-8	34-55-21	D00169C		12	DN	D02849		=A1		ALL
0061		22		PA		2-3	23-51-51	D04031P		15		D41557P		7		ALL
0069		24		PK		1-11	34-53-21	D00155A		C03		TB1504Y	A013	1A		ALL
006CO					BF	0-0	34-55-21	D00169B		=C71		D41515P		=C1		ALL
006CX				OH	BF	1-11	34-55-21	D00169B		71		D41515P		=A1		ALL
0070		24		PK		1-11	34-53-21	D00155A		E03		TB1504Y	A013	1A		ALL
0071		24		PK		1-11	34-53-21	D00155A		F03		TB1504Y	A013	1A		ALL
0072		22		PA		2-0	23-12-21	D00201B		C11		GD01503	DC..	1A		YD158-YR328
0073		22		PA		2-9	34-51-41	D04031P		10		D45125P		5		YL951-YR328
0074		22		PA		2-8	34-51-41	D04031P		11		TB1504W	B005	1		YL951-YR328
0075		22		PA		2-1	34-51-41	D45125P		4		TB1504W	B005	1		YL951-YR328
007CO					BG	0-0	23-12-21	D00201C		=C1		D04131P		=C1		ALL
007CX				OF	BG	1-5	23-12-21	D00201C		1	DN	D04131P		=A1		ALL
0083		24		PK		2-8	23-12-41	D00201B		D11		D04125P		8		YD158-YR328
0084		24		G6		0-7	23-12-21	D00201B		A09		D00201B		C09		YD158-YD170
0084		24		PK		0-7	23-12-21	D00201B		A09		D00201B		C09		YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0150

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0151	286A0151			E1-5 SHELF (continued)											
0201	24		PK		3-0	34-53-21	D00155B	A01			D41507P	1			ALL
0202	24		PK		3-0	34-53-21	D00155B	B01			D41507P	2			ALL
0203	24		PK		3-0	34-53-21	D00155B	C01			D41507P	3			ALL
0204	24		PK		3-0	34-53-21	D00155B	D01			D41507P	4			ALL
0205	24		PK		3-0	34-53-21	D00155B	E01			D41507P	5			ALL
0206	24		PK		3-0	34-53-21	D00155B	F01			D41507P	6			ALL
0207	24		PK		3-0	34-53-21	D00155B	G01			D41507P	7			ALL
0208	24		PK		3-0	34-53-21	D00155B	H01			D41507P	8			ALL
0209	24		PK		3-0	34-53-21	D00155B	J01			D41507P	9			ALL
0210	24		PK		3-0	34-53-21	D00155B	K01			D41507P	10			ALL
0211	24		PK		3-0	34-53-21	D00155B	A02			D41507P	11			ALL
0212	24		PK		3-0	34-53-21	D00155B	B02			D41507P	12			ALL
0213	24		PK		3-0	34-53-21	D00155B	C02			D41507P	13			ALL
0214	24		PK		3-0	34-53-21	D00155B	D02			D41507P	14			ALL
0215	24		PK		3-0	34-53-21	D00155B	E02			D41507P	15			ALL
0216	24		PK		3-0	34-53-21	D00155B	F02			D41507P	16			ALL
0217	24		PK		3-0	34-53-21	D00155B	G02			D41507P	17			ALL
0218	24		PK		3-0	34-53-21	D00155B	H02			D41507P	18			ALL
0219	24		PK		3-0	34-53-21	D00155B	J02			D41507P	19			ALL
0220	24		PK		3-0	34-53-21	D00155B	K02			D41507P	20			ALL
0221	24		PK		3-0	34-53-21	D00155B	A03			D41507P	21			ALL
0222	24		PK		3-0	34-53-21	D00155B	B03			D41507P	22			ALL
0223	24		PK		3-0	34-53-21	D00155B	C03			D41507P	23			ALL
0224	24		PK		3-0	34-53-21	D00155B	D03			D41507P	24			ALL
0225	24		PK		3-0	34-53-21	D00155B	E03			D41507P	25			ALL
0226	24		PK		1-9	34-53-21	D00155A	D05			TB1504Y	B001	1A		YC051-YD157
0226	24		PK		1-8	34-53-21	D00155A	D05			TB1504Y	B001	1A		YD158-YR328
0227	24		PK		1-9	34-53-21	D00155A	C05			TB1504Y	B001	1A		YC051-YD157
0227	24		PK		1-8	34-53-21	D00155A	C05			TB1504Y	B001	1A		YD158-YR328
0228	24		PK		1-8	34-53-21	D00155B	J05			TB1504Y	B001	1A		YC051-YD157
0228	24		PK		1-7	34-53-21	D00155B	J05			TB1504Y	B001	1A		YD158-YR328
2001B	24		Y2	A	2-11	34-53-21	D41517P	14			D00155A	F07			YC051-YD157
2001B	24		Y2	A	2-10	34-53-21	D41517P	14			D00155A	F07			YD158-YR328
2001R	24		Y2	A	0-0	34-53-21	D41517P	13			D00155A	E07			ALL
2001Z				A	0-0	34-53-21	D41517P	S/R			GB01504	ST..	1A		ALL
2002B	24		Y2	RZ	2-11	34-21-23	D00155A	D02			D41557P	18			YD158-YR328
2002R	24		Y2	RZ	0-0	34-21-23	D00155A	C02			D41557P	17			YD158-YR328
2002Z				RZ	0-0	34-21-23	GB01504	ST..	1A		D41557P	S/R			YD158-YR328
2003B	24		M5	C	2-3	23-22-11	D00201B	B13			D04197P	10			ALL

WIRE LIST

D280A108

91-21-11
Section W0150
Page 3
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W0151	286A0151	E1-5 SHELF (continued)													
2003R	24	M5	C	0-0	23-22-11	D00201B	A13		D04197P	9			ALL		
2003ZI			C	0-0	23-22-11	D00201B	DED		D04197P	11			ALL		
2003ZO			C	0-0	23-22-11	D00201B	PERG	1A	D04197P	S/R			ALL		
2004B	24	Y2	D	2-11	34-45-21	D00155A	F05		D41557P	14			ALL		
2004R	24	Y2	D	0-0	34-45-21	D00155A	E05		D41557P	13			ALL		
2004Z			D	0-0	34-45-21	GB01504	ST..	1A	D41557P	S/R			ALL		
2005B	24	Y2	E	2-11	34-45-21	D00155A	H05		D41557P	2			YC051-YD157		
2005B	24	Y2	E	1-10	34-45-21	D00155A	H05		TB1504Y	B011	1A		YD158-YR328		
2005R	24	Y2	E	0-0	34-45-21	D00155A	G05		D41557P	1			YC051-YD157		
2005R	24	Y2	E	0-0	34-45-21	D00155A	G05		TB1504Y	A011	1A		YD158-YR328		
2005Z			E	0-0	34-45-21	GB01504	ST..	1A	D41557P	S/R			YC051-YD157		
2005Z			E	0-0	34-45-21	GB01504	ST..	1A	D00155A	DED			YD158-YR328		
2006B	24	Y2	F	1-8	34-55-21	D00169B	E03		TB1501Y	B001	1A		ALL		
2006R	24	Y2	F	0-0	34-55-21	D00169B	D03		TB1501Y	A001	1A		ALL		
2006Z			F	0-0	34-55-21	D00169B	DED		GB01501	ST..	1A		ALL		
2007B	24	Y2	G	3-2	34-55-21	D04031P	25		TB1501Y	B001	1A		ALL		
2007R	24	Y2	G	0-0	34-55-21	D04031P	24		TB1501Y	A001	1A		ALL		
2007Z			G	0-0	34-55-21	D04031P	S/R		GB01501	ST..	1A		ALL		
2008B	24	Y2	H	2-11	34-55-21	D00169B	H03		D45125P	23			ALL		
2008R	24	Y2	H	0-0	34-55-21	D00169B	G03		D45125P	22			ALL		
2008Z			H	0-0	34-55-21	GB01501	ST..	1A	D45125P	S/R			ALL		
2009B	24	M5	J	3-1	34-55-21	D00169B	B01		D04197P	13			ALL		
2009R	24	M5	J	0-0	34-55-21	D00169B	A01		D04197P	12			ALL		
2009ZI			J	0-0	34-55-21	D00169B	DED		D04197P	14			ALL		
2009ZO			J	0-0	34-55-21	GB01501	ST..	1A	D04197P	S/R			ALL		
2010B	24	Y2	K	2-9	34-51-21	D04031P	21		D45125P	21			ALL		
2010R	24	Y2	K	0-0	34-51-21	D04031P	20		D45125P	20			ALL		
2010Z			K	0-0	34-51-21	D04031P	S/R		D45125P	S/R			ALL		
2011B	24	Y2	AL	1-9	34-55-21	D00169B	H01		TB1501Y	B005	1A		ALL		
2011R	24	Y2	AL	0-0	34-55-21	D00169B	G01		TB1501Y	A005	1A		ALL		
2011Z			AL	0-0	34-55-21	D00169B	DED		GB01501	ST..	1A		ALL		
2012B	24	Y2	M	2-8	34-55-21	D45125P	25		TB1501Y	B005	1A		ALL		
2012R	24	Y2	M	0-0	34-55-21	D45125P	24		TB1501Y	A005	1A		ALL		
2012Z			M	0-0	34-55-21	D45125P	S/R		GB01501	ST..	1A		ALL		
2013B	24	Y2	N	3-0	34-55-21	D41557P	6		TB1501Y	B005	1A		ALL		
2013R	24	Y2	N	0-0	34-55-21	D41557P	5		TB1501Y	A005	1A		ALL		
2013Z			N	0-0	34-55-21	D41557P	S/R		GB01501	ST..	1A		ALL		
2014B	24	Y2	P	2-11	34-51-21	D00169B	B03		D45125P	31			ALL		
2014R	24	Y2	P	0-0	34-51-21	D00169B	A03		D45125P	30			ALL		

WIRE LIST

D280A108

91-21-11

Section W0150

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0151	286A0151				E1-5 SHELF (continued)										
2014Z				P	0-0	34-51-21	GB01501	ST..	1A		D45125P	S/R			ALL
2015B	24	Y2	Q		2-8	34-55-21	D45125P	27			TB1501Y	B005	1A		ALL
2015R	24	Y2	Q		0-0	34-55-21	D45125P	26			TB1501Y	A005	1A		ALL
2015Z				Q	0-0	34-55-21	D45125P	S/R			GB01501	ST..	1A		ALL
2016B	24	Y2	R		3-0	34-21-14	D00155B	B05			D41507P	34			ALL
2016R	24	Y2	R		0-0	34-21-14	D00155B	A05			D41507P	33			ALL
2016Z				R	0-0	34-21-14	GB01504	ST..	1A		D41507P	S/R			ALL
2017B	24	Y2	S		2-7	34-21-24	D41507P	36			TB1504Y	B003	1A		ALL
2017R	24	Y2	S		0-0	34-21-24	D41507P	35			TB1504Y	A003	1A		ALL
2017Z				S	0-0	34-21-24	D41507P	S/R			GB01504	ST..	1A		ALL
2018B	24	Y2	T		2-5	34-21-24	D41557P	9			TB1504Y	B003	1A		ALL
2018R	24	Y2	T		0-0	34-21-24	D41557P	8			TB1504Y	A003	1A		ALL
2018Z				T	0-0	34-21-24	D41557P	S/R			GB01504	ST..	1A		ALL
2019B	24	Y2	U		1-9	34-21-24	D00155A	J07			TB1504Y	B003	1A		YC051-YD157
2019B	24	Y2	U		1-8	34-21-24	D00155A	J07			TB1504Y	B003	1A		YD158-YR328
2019R	24	Y2	U		0-0	34-21-24	D00155A	H07			TB1504Y	A003	1A		ALL
2019Z				U	0-0	34-21-24	D00155A	DED			GB01504	ST..	1A		ALL
2020B	24	Y2	V		3-0	34-61-14	D41557P	16			TB1501Y	B001	1A		ALL
2020R	24	Y2	V		0-0	34-61-14	D41557P	15			TB1501Y	A001	1A		ALL
2020Z				V	0-0	34-61-14	D41557P	S/R			GB01501	ST..	1A		ALL
2021B	24	Y2	X		2-9	22-11-51	D04031P	18			D45125P	29			ALL
2021R	24	Y2	X		0-0	22-11-51	D04031P	17			D45125P	28			ALL
2021Z				X	0-0	22-11-51	D04031P	S/R			D45125P	S/R			ALL
2022B	24	Y2	Y		2-9	34-31-21	D04031P	29			D45125P	33			ALL
2022R	24	Y2	Y		0-0	34-31-21	D04031P	28			D45125P	32			ALL
2022Z				Y	0-0	34-31-21	D04031P	S/R			D45125P	S/R			ALL
2023B	24	Y2	B		2-6	34-45-21	D41557P	2			TB1504Y	B011	1A		YD158-YR328
2023R	24	Y2	B		0-0	34-45-21	D41557P	1			TB1504Y	A011	1A		YD158-YR328
2023Z				B	0-0	34-45-21	D41557P	S/R			GB01504	ST..	1A		YD158-YR328
2024B	24	Y2	L		2-2	34-45-21	D45125P	19			TB1504Y	B011	1A		YD158-YD170
2024R	24	Y2	L		0-0	34-45-21	D45125P	18			TB1504Y	A011	1A		YD158-YD170
2024Z				L	0-0	34-45-21	D45125P	S/R			GB01504	ST..	1A		YD158-YD170
2031B	24	Y2	AG		2-8	23-12-21	D00201B	B07			D04125P	2			YC051-YD157
2031B	24	Y2	AG		2-8	23-12-41	D00201B	B07			D04125P	6			YD158-YR328
2031R	24	Y2	AG		0-0	23-12-21	D00201B	A07			D04125P	1			YC051-YD157
2031R	24	Y2	AG		0-0	23-12-41	D00201B	A07			D04125P	5			YD158-YR328
2031Z				AG	0-0	23-12-21	D00201B	PERG	1A		D04125P	S/R			YC051-YD157
2031Z				AG	0-0	23-12-41	D00201B	PERG	1A		D04125P	S/R			YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0150

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W0151	286A0151			E1-5 SHELF (continued)											
2034B	24	Y2	AC		2-8	23-12-41	D00201B	B11			D04125P	2			YD158-YL999, YN501-YR328
2034B	24	Y2	AN		2-8	23-12-41	D00201B	B11			D04125P	2			YN231-YN260
2034R	24	Y2	AC		0-0	23-12-41	D00201B	A11			D04125P	1			YD158-YL999, YN501-YR328
2034R	24	Y2	AN		0-0	23-12-41	D00201B	A11			D04125P	1			YN231-YN260
2034Z			AC		0-0	23-12-41	D00201B	PERG	1A		D04125P	S/R			YD158-YL999, YN501-YR328
2034Z			AN		0-0	23-12-41	D00201B	PERG	1A		D04125P	S/R			YN231-YN260
2041B	24	Y2	AW		2-8	23-12-21	D00201B	D14			D04125P	4			YD158-YR328
2041R	24	Y2	AW		0-0	23-12-21	D00201B	C14			D04125P	3			YD158-YR328
2041Z			AW		0-0	23-12-21	D00201B	DED			D04125P	S/R			YD158-YD170, YN231-YN260
2041Z			AW		0-0	23-12-21	D00201B	PERG	1A		D04125P	S/R			YL951-YL999, YN501-YR328
2044B	24	Y2	AB		3-1	23-27-37	D41507P	40			D00155A	REF	VP		YD158-YL999
2044B	24	Y2	AA		3-1	23-27-37	D00155A	REF	VP		D41507P	40			YN231-YN260
2044R	24	Y2	AB		0-0	23-27-37	D41507P	39			D00155A	REF	VP		YD158-YL999
2044R	24	Y2	AA		0-0	23-27-37	D00155A	REF	VP		D41507P	39			YN231-YN260
2044Z			AB		0-0	23-27-37	D41507P	S/R			D00155A	DED			YD158-YL999
2044Z			AA		0-0	23-27-37	D00155A	DED			D41507P	S/R			YN231-YN260
2046B	24	Y2	BM		2-7	23-27-37	D41507P	46			D00201B	B12	VP		YD158-YL999
2046B	24	Y2	AD		2-7	23-27-37	D00201B	B12	VP		D41507P	46			YN231-YR328
2046R	24	Y2	BM		0-0	23-27-37	D41507P	45			D00201B	A12	VP		YD158-YL999
2046R	24	Y2	AD		0-0	23-27-37	D00201B	A12	VP		D41507P	45			YN231-YR328
2046Z			BM		0-0	23-27-37	D41507P	S/R			D00201B	DED			YD158-YL999
2046Z			AD		0-0	23-27-37	D00201B	DED			D41507P	S/R			YN231-YR328
2048B	24	Y2	AK		2-8	34-45-21	D41507P	42			TB1504Y	B011	1A		YL951-YL999, YR301-YR328
2048B	24	Y2	AF		2-8	34-45-21	D41507P	42			TB1504Y	B011	1A		YN231-YN501
2048R	24	Y2	AK		0-0	34-45-21	D41507P	41			TB1504Y	A011	1A		YL951-YL999, YR301-YR328
2048R	24	Y2	AF		0-0	34-45-21	D41507P	41			TB1504Y	A011	1A		YN231-YN501
2048Z			AK		0-0	34-45-21	D41507P	S/R			GB01504	ST..	1A		YL951-YL999, YR301-YR328
2048Z			AF		0-0	34-45-21	D41507P	S/R			GB01504	ST..	1A		YN231-YN501
2050B	24	Y2	AH		2-7	23-27-37	D41507P	50			D00201B	D10	VP		YD158-YD170
2050B	24	Y2	CC		2-7	23-27-37	D41507P	50			D00201B	D10	VP		YL951-YL999
2050B	24	Y2	AE		2-7	23-27-37	D00201B	D10	VP		D41507P	50			YN231-YR328

WIRE LIST

D280A108

91-21-11

Section W0150

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0151	286A0151			E1-5 SHELF (continued)											
2050R	24	Y2		AH	0-0	23-27-37	D41507P	49			D00201B	C10	VP		YD158-YD170
2050R	24	Y2		CC	0-0	23-27-37	D41507P	49			D00201B	C10	VP		YL951-YL999
2050R	24	Y2		AE	0-0	23-27-37	D00201B	C10	VP		D41507P	49			YN231-YR328
2050Z				AH	0-0	23-27-37	D41507P	S/R			D00201B	DED			YD158-YD170
2050Z				CC	0-0	23-27-37	D41507P	S/R			D00201B	DED			YL951-YL999
2050Z				AE	0-0	23-27-37	D00201B	DED			D41507P	S/R			YN231-YR328
2056B	24	Y2		RX	2-11	22-11-51	D00155A	B07			D41557P	30			YD158-YR328
2056R	24	Y2		RX	0-0	22-11-51	D00155A	A07			D41557P	29			YD158-YR328
2056Z				RX	0-0	22-11-51	GB01504	ST..	1A		D41557P	S/R			YD158-YR328
2058B	24	Y2		CZ	2-1	34-61-14	D00155A	B06			TB1501Y	B001	1A		YD158-YD170
2058B	24	Y2		DM	2-1	34-61-14	D00155A	B06			TB1501Y	B001	1A		YL951-YR328
2058R	24	Y2		CZ	0-0	34-61-14	D00155A	A06			TB1501Y	A001	1A		YD158-YD170
2058R	24	Y2		DM	0-0	34-61-14	D00155A	A06			TB1501Y	A001	1A		YL951-YR328
2058Z				CZ	0-0	34-61-14	GB01501	ST..	1A		GB01504	ST..	1A		YD158-YD170
2058Z				DM	0-0	34-61-14	GB01501	ST..	1A		GB01504	ST..	1A		YL951-YR328
2059B	22	X2		DJ	3-1	34-53-21	D00155A	B02			D41507P	52			YD158-YR328
2059R	22	X2		DJ	0-0	34-53-21	D00155A	A02			D41507P	51			YD158-YR328
2059Z				DJ	0-0	34-53-21	GB01504	ST..	1A		D41507P	S/R			YD158-YR328
2507B	24	M5		CG	2-3	23-12-21	D00201B	B01			D04197P	2			ALL
2507R	24	M5		CG	0-0	23-12-21	D00201B	A01			D04197P	1			ALL
2507ZI				CG	0-0	23-12-21	D00201B	DED			D04197P	3			ALL
2507ZO				CG	0-0	23-12-21	D00201B	PERG	1A		D04197P	S/R			ALL
2508B	24	M5		CH	2-3	23-12-21	D00201B	B15			D04197P	5			ALL
2508R	24	M5		CH	0-0	23-12-21	D00201B	A15			D04197P	4			ALL
2508ZI				CH	0-0	23-12-21	D00201B	DED			D04197P	6			ALL
2508ZO				CH	0-0	23-12-21	D00201B	PERG	1A		D04197P	S/R			ALL
W0152	286A0152			AFT ENTRY LIGHT PANEL											
0001	20	PA			8-1	33-29-11	D40026J	1			D11460	1			YC051-YN260
0002	20	PA			8-1	33-29-11	D40026J	2			D11460	2			YC051-YN260
0003	20	PA			3-5	33-51-14	D10180	7			D40026J	3			ALL
0004	20	PA			3-5	33-51-14	D10180	8			D40026J	4			ALL
0005	20	PA			8-1	33-29-11	D40026J	5			D11460	5			YC051-YN260
0005	24	PK			9-6	33-29-11	D40026J	5			D14776	A			YN501-YR328
0006	20	PA			8-1	33-29-11	D40026J	6			D11460	6			YC051-YN260
0006	24	PK			9-6	33-29-11	D40026J	6			D14776	B			YN501-YR328
0007	20	PA			8-1	33-29-11	D40026J	7			D11460	7			YC051-YN260
0008	22	PA			8-1	33-29-11	D40026J	8			D11460	8			YC051-YN260
0009	22	PA			3-5	33-27-22	D40026J	9			D10180	2			ALL

WIRE LIST

D280A108

91-21-11

Section W0150

Page 7

Nov 12/2012

Bundle No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice
Wire No.															
W0152	286A0152				AFT ENTRY LIGHT PANEL (continued)										
0010	22	PA			3-5	33-27-22	D40026J	10				D10180	3		ALL
0011	18	PA			7-8	35-21-21	D11480	1				SM00001		S	YC051-YN260
0011	18	PA			7-9	35-21-21	D11480	1				SM00001		S	YN501-YR328
0012	18	PA			7-8	35-21-21	D11480	2				SM00002		S	YC051-YN260
0012	18	PA			7-9	35-21-21	D11480	2				SM00002		S	YN501-YR328
0013	22	PA			8-1	33-29-11	D40026J	13				D11460	3		YC051-YN260
0014	20	PA			8-1	33-29-11	D40026J	14				D11460	4		YC051-YN260
0017	22	PA			3-5	SPARE	D40026J	17				D10180	5		ALL
0018	22	PA			3-5	SPARE	D40026J	18				D10180	1		ALL
0021	18	PA			2-6	35-21-21	D40032J	1				SM00001		S	ALL
0022	18	PA			2-6	35-21-21	D40032J	2				SM00002		S	ALL
0024	22	PA			3-5	23-42-11	D40026J	15				D10180	4		ALL
0026	22	PA			3-5	23-42-11	D40026J	16				D10180	6		ALL
0031	18	PA			1-0	35-21-21	D11368	1				SM00001		S	YC051-YN260
0031	18	PA			1-1	35-21-21	D11368	1				SM00001		S	YN501-YR328
0032	18	PA			1-0	35-21-21	D11368	2				SM00002		S	YC051-YN260
0032	18	PA			1-1	35-21-21	D11368	2				SM00002		S	YN501-YR328
3403B	20	PC	C2		10-4	23-41-11	D40032J	5				SM00005		S	ALL
3403R	20	PC	C2		0-0	23-41-11	D40032J	4				SM00004		S	ALL
3403Y	20	PC	C2		0-0	23-41-11	D40032J	3				SM00003		S	ALL
A-A					0-0	23-41-11	SM00003		S			D06015	BLK		ALL
A-B					0-0	23-41-11	SM00004		S			D06015	RED		ALL
A-C					0-0	23-41-11	SM00005		S			D06015	BLU		ALL
W0154	286A0154				AFT RECESSED LIGHT PANEL										
0001	18	PA			7-7	33-22-22	D11382	1				SM00001		S	YC051-YN260
0002	18	PA			7-7	33-22-22	D11382	2				SM00002		S	YC051-YN260
0003	18	PA			7-7	33-22-22	D11382	3				SM00003		S	YC051-YN260
0005	24	PK			6-8	33-22-22	D11382	5				SM00005		S	YC051-YD170
0005	24	PK			7-7	33-22-22	D11382	5				SM00005		S	YL951-YN260
0006	24	PK			6-8	33-22-22	D11382	6				SM00006		S	YC051-YD170
0006	24	PK			7-7	33-22-22	D11382	6				SM00006		S	YL951-YN260
0007	20	PA			3-10	33-26-31	D40038J	7				D11358	1		YC051-YN260
0008	20	PA			3-10	33-26-31	D40038J	8				D11358	2		YC051-YN260
0009	20	PA			3-10	33-26-31	D40038J	9				D11358	3		YC051-YN260
0011	18	PA			2-1	33-22-22	D11394	1				SM00001		S	YC051-YN260
0012	18	PA			2-1	33-22-22	D11394	2				SM00002		S	YC051-YN260
0013	18	PA			2-1	33-22-22	D11394	3				SM00003		S	YC051-YN260
0015	24	PK			1-11	33-22-22	D11394	5				SM00005		S	YC051-YD170

WIRE LIST

D280A108

91-21-11

Section W0150

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W0154	286A0154				AFT RECESSED LIGHT PANEL (continued)											
0015	24		PK		2-1	33-22-22	D11394		5			SM00005		S		YL951-YN260
0016	24		PK		1-11	33-22-22	D11394		6			SM00006		S		YC051-YD170
0016	24		PK		2-1	33-22-22	D11394		6			SM00006		S		YL951-YN260
0021	18		PA		1-0	33-22-22	D40038J		1			SM00001		S		YC051-YN260
0022	18		PA		1-0	33-22-22	D40038J		2			SM00002		S		YC051-YN260
0023	18		PA		1-0	33-22-22	D40038J		3			SM00003		S		YC051-YN260
0025	24		PK		1-11	33-22-22	D40038J		5			SM00005		S		YC051-YD170
0025	24		PK		1-0	33-22-22	D40038J		5			SM00005		S		YL951-YN260
0026	24		PK		1-11	33-22-22	D40038J		6			SM00006		S		YC051-YD170
0026	24		PK		1-0	33-22-22	D40038J		6			SM00006		S		YL951-YN260
0040	20		PA		6-3	33-51-14	D40038J		10			L01419	1	C		YL951-YN260
0041	20		PA		6-3	33-51-14	D40038J		11			L01419	2	C		YL951-YN260
W0156	286A0156				FORWARD COVE LIGHTS											
0001	18		PA		3-6	33-24-21	D14610		B			SM00001		S		YN501-YR328
0002	18		PA		4-7	33-24-21	D14610		C			D41072J	2			YN501-YR328
0003	18		PA		4-7	33-24-21	D14610		A			D41072J	5			YN501-YR328
0004	18		PA		1-8	33-24-21	D41072J		1			SM00001		S		YN501-YR328
0006	18		PA		0-10	33-24-21	SM00001		S			SM00002		S		YN501-YR328
0011	18		PA		1-4	33-24-21	D14634		B			SM00002		S		YN501-YR328
0012	18		PA		2-5	33-24-21	D14634		C			D41072J	4			YN501-YR328
0013	18		PA		2-5	33-24-21	D14634		A			D41072J	3			YN501-YR328
0021	18		PA		4-2	33-24-21	D14630		B			SM00002		S		YN501-YR328
0022	18		PA		5-3	33-24-21	D14630		C			D41072J	6			YN501-YR328
0023	18		PA		5-3	33-24-21	D14630		A			D41072J	7			YN501-YR328
0031	18		PA		3-10	33-24-21	D14650		B			SM00002		S		YN501-YR328
0032	18		PA		4-11	33-24-21	D14650		C			D41072J	8			YN501-YR328
0033	18		PA		4-11	33-24-21	D14650		A			D41072J	9			YN501-YR328
2001B	24		OT	EA	4-7	33-24-21	D14474		2			D14478	2			YN501-YR328
2001W	24		OT	EA	0-0	33-24-21	D14474		1			D14478	1			YN501-YR328
2001Z				EA	0-0	33-24-21	D14474		5			D14478	5			YN501-YR328
2002B	24		PL	EB	4-7	33-24-21	D14474		4			D14478	4			YN501-YR328
2002R	24		PL	EB	0-0	33-24-21	D14474		3			D14478	3			YN501-YR328
W0158	286A0158				AFT COVE LIGHTS - PANEL 1											
0001	18		PA		2-0	33-24-22	D14654		B			SM00001		S		YN501-YR328
0002	18		PA		4-3	33-24-22	D14654		C			D41074J	2			YN501-YR328
0003	18		PA		4-3	33-24-22	D14654		A			D41074J	5			YN501-YR328
0004	18		PA		4-3	33-24-22	D41074J		1			SM00001		S		YN501-YR328

WIRE LIST
D280A108

91-21-11
Section W0150
Page 9
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0158		286A0158					AFT COVE LIGHTS - PANEL 1 (continued)									
0005		18		PA		4-4	33-24-22	D14546		B		SM00001		S		YN501-YR328
0008		20		PA		5-3	33-26-31	D41074J		8		L01146	=G	Z		YN501-YR328
0009		20		PA		5-4	33-26-31	D41074J		9		L01146	=P	Z3		YN501-YR328
0011		18		PA		2-6	33-24-22	D14614		B		SM00001		S		YN501-YR328
0012		18		PA		4-2	33-24-22	D14614		C		D41074J	4			YN501-YR328
0013		18		PA		4-2	33-24-22	D14614		A		D41074J	3			YN501-YR328
0021		18		PA		4-4	33-24-22	D14626		B		SM00001		S		YN501-YR328
0022		18		PA		8-6	33-24-22	D14626		C		D41074J	6			YN501-YR328
0023		18		PA		8-6	33-24-22	D14626		A		D41074J	7			YN501-YR328
2001B		24		OT	EA	4-5	33-24-22	D14540		2		D14544	2			YN501-YR328
2001W		24		OT	EA	0-0	33-24-22	D14540		1		D14544	1			YN501-YR328
2001Z					EA	0-0	33-24-22	D14540		5		D14544	5			YN501-YR328
2002B		24		PL	EB	4-5	33-24-22	D14540		4		D14544	4			YN501-YR328
2002R		24		PL	EB	0-0	33-24-22	D14540		3		D14544	3			YN501-YR328
2003B		24		OT	EC	2-3	33-24-22	D14568		2		D14792	2			YN501-YR328
2003W		24		OT	EC	0-0	33-24-22	D14568		1		D14792	1			YN501-YR328
2003Z					EC	0-0	33-24-22	D14568		5		D14792	5			YN501-YR328
2004B		24		PL	ED	2-3	33-24-22	D14568		4		D14792	4			YN501-YR328
2004R		24		PL	ED	0-0	33-24-22	D14568		3		D14792	3			YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0150

Page 10 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I W0160	286A0160			AFT COVE LIGHTS - PANEL 2											
I 0001	18		PA		2-6	33-24-22	D14618		B		SM00001		S		YN501-YR328
I 0002	18		PA		1-9	33-24-22	D14618		C		SM00003		S		YN501-YR328
I 0003	18		PA		1-9	33-24-22	D14618		A		SM00002		S		YN501-YR328
I 0004	18		PA		7-7	33-24-22	D14550		B		SM00001		S		YN501-YR328
I 0005	18		PA		2-2	33-24-22	D41078J		A		SM00002		S		YN501-YR328
I 0006	18		PA		2-2	33-24-22	D41078J		C		SM00003		S		YN501-YR328
I 0011	18		PA		1-8	33-24-22	D14622		B		SM00001		S		YN501-YR328
I 0012	18		PA		2-3	33-24-22	D14622		C		SM00003		S		YN501-YR328
I 0013	18		PA		2-3	33-24-22	D14622		A		SM00002		S		YN501-YR328
I 2001B	24		OT	EA	8-9	33-24-22	D14788		2		D14552	2			YN501-YR328
I 2001W	24		OT	EA	0-0	33-24-22	D14788		1		D14552	1			YN501-YR328
I 2001Z				EA	0-0	33-24-22	D14788		5		D14552	5			YN501-YR328
I 2002B	24		PL	EB	8-9	33-24-22	D14788		4		D14552	4			YN501-YR328
I 2002R	24		PL	EB	0-0	33-24-22	D14788		3		D14552	3			YN501-YR328
I 2003B	24		OT	EC	2-8	33-24-22	D14556		2		D14560	2			YN501-YR328
I 2003W	24		OT	EC	0-0	33-24-22	D14556		1		D14560	1			YN501-YR328
I 2003Z				EC	0-0	33-24-22	D14556		5		D14560	5			YN501-YR328
I 2004B	24		PL	ED	2-8	33-24-22	D14556		4		D14560	4			YN501-YR328
I 2004R	24		PL	ED	0-0	33-24-22	D14556		3		D14560	3			YN501-YR328
I 2005B	24		OT	EE	8-10	33-24-22	D14564		2		D14790	2			YN501-YR328
I 2005W	24		OT	EE	0-0	33-24-22	D14564		1		D14790	1			YN501-YR328
I 2005Z				EE	0-0	33-24-22	D14564		5		D14790	5			YN501-YR328
I 2006B	24		PL	EF	8-10	33-24-22	D14564		4		D14790	4			YN501-YR328
I 2006R	24		PL	EF	0-0	33-24-22	D14564		3		D14790	3			YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0160

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0204		286A0204					P7 FIRST OFFICER'S GLARESHIELD PANEL (SN2)									
0001		24		PK		2-4	23-51-21	D40740P	19			S00989	1C	Z2		YL951-YR328
0002		24		PK		2-4	23-51-21	D40740P	20			S00989	1NO	Z2		YL951-YR328
1001		20		X1	AA	2-9	31-52-11	L00344	C	\$		D40740P	4			YC051-YD158
1001		20		X1	AA	2-1	31-52-11	D14116	3			D40740P	4			YL951-YR328
1001Z					AA	0-0	31-52-11	D40740P	DED			L00344	DED			YC051-YD158
1001Z					AA	0-0	31-52-11	D14116	DED			D40740P	DED			YL951-YR328
1002		20		X1	AB	2-9	31-52-11	L00344	A	\$		D40740P	6			YC051-YD158
1002		20		X1	AB	2-1	31-52-11	D14116	1			D40740P	6			YL951-YR328
1002Z					AB	0-0	31-52-11	D40740P	DED			L00344	DED			YC051-YD158
1002Z					AB	0-0	31-52-11	D14116	DED			D40740P	DED			YL951-YR328
1003		20		X1	AC	2-9	31-52-11	L00344	B	\$		D40740P	7			YC051-YD158
1003		20		X1	AC	2-1	31-52-11	D14116	2			D40740P	7			YL951-YR328
1003Z					AC	0-0	31-52-11	D40740P	DED			L00344	DED			YC051-YD158
1003Z					AC	0-0	31-52-11	D14116	DED			D40740P	DED			YL951-YR328
1004		20		X1	AD	2-9	31-52-11	L00344	NC	\$		D40740P	5			YC051-YD158
1004		20		X1	AD	2-1	31-52-11	D14116	4			D40740P	5			YL951-YR328
1004Z					AD	0-0	31-52-11	D40740P	DED			L00344	DED			YC051-YD158
1004Z					AD	0-0	31-52-11	D14116	DED			D40740P	DED			YL951-YR328
5501		20		PA		3-4	31-52-11	L00343	7	B		D40740P	1			YC051-YD157
5501		20		PA		3-4	31-52-11	L00343	7	C		D40740P	1			YD158, YL951-YR328
5502		20		PA		3-4	31-52-11	L00343	8	B		D40740P	2			YC051-YD157
5502		20		PA		3-4	31-52-11	L00343	8	C		D40740P	2			YD158, YL951-YR328
5503		20		CQ		3-4	31-52-11	L00343	9	B		D40740P	3			YC051-YD157
5503		20		CQ		3-4	31-52-11	L00343	9	C		D40740P	3			YD158, YL951-YR328
5508		20		CQ		3-4	31-52-55	L00343	1	B		D40740P	8			YC051-YD157
5508		20		CQ		3-4	31-52-55	L00343	1	C		D40740P	8			YD158, YL951-YR328
5509		20		CQ		3-4	31-52-21	L00343	2	B		D40740P	9			YC051-YD157
5509		20		CQ		3-4	31-52-21	L00343	2	C		D40740P	9			YD158, YL951-YR328
5510		20		CQ		3-4	31-52-65	L00343	3	B		D40740P	10			YC051-YD157
5510		20		CQ		3-4	31-52-65	L00343	3	C		D40740P	10			YD158, YL951-YR328
5511		20		CQ		3-4	31-52-61	L00343	4	B		D40740P	11			YC051-YD157
5511		20		CQ		3-4	31-52-61	L00343	4	C		D40740P	11			YD158, YL951-YR328
5512		20		CQ		3-4	31-52-75	L00343	5	B		D40740P	12			YC051-YD157
5512		20		CQ		3-4	31-52-75	L00343	5	C		D40740P	12			YD158, YL951-YR328
5513		20		CQ		3-4	31-52-51	L00343	6	B		D40740P	13			YC051-YD157
5513		20		CQ		3-4	31-52-51	L00343	6	C		D40740P	13			YD158, YL951-YR328
5514R		22		PH		2-9	26-11-21	L00345	NO	\$		D40740P	14			YC051-YD158
5514R		22		PH		2-1	26-11-21	D14120	4			D40740P	14			YL951-YR328
5515R		22		PH		2-9	26-11-21	L00345	C	\$		D40740P	15			YC051-YD158

WIRE LIST

D280A108

91-21-11

Section W0200

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To					
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W0204	286A0204				P7 FIRST OFFICER'S GLARESHIELD PANEL (SN2) (continued)											
5515R	22		PH		2-1	26-11-21	D14120		3			D40740P	15			YL951-YR328
5516R	22		PH		2-9	26-11-21	L00345		B	\$		D40740P	16			YC051-YD158
5516R	22		PH		2-1	26-11-21	D14120		2			D40740P	16			YL951-YR328
5517	20		CQ		2-2	33-14-11	D11926		= 1			D40740P	36			YC051-YD158, YL951-YR328
5518	20		CQ		2-2	33-14-11	D11928		= 1			D40740P	37			YC051-YD158, YL951-YR328
5519	20		CQ		2-9	33-14-11	D11940		= 1			D40740P	38			YC051-YD158, YL951-YR328
5520	20		CQ		2-10	33-14-11	D11942		= 1			D40740P	39			YC051-YD158, YL951-YR328
5521R	20		PH		2-9	33-18-51	L00345		A	\$		D40740P	21			YC051-YD158
5521R	20		PH		2-1	33-18-51	D14120		1			D40740P	21			YL951-YR328
5527	20		CQ		2-5	33-11-21	D40740P		17			L01241	= P	B		YL951-YR328
5528	20		CQ		2-5	33-11-21	D40740P		18			L01241	= G	G		YL951-YR328
A-AA					0-0	31-62-21	T00508		RED			D40740P	22			YC051-YD158, YL951-YR328
A-AB					0-0	31-62-21	T00508		BLU			D40740P	23			YC051-YD158, YL951-YR328
A-AC					0-0	31-62-21	T00508		YEL			D40740P	24			YC051-YD158, YL951-YR328
A-AD					0-0	31-62-21	T00508		BRN			D40740P	25			YC051-YD158, YL951-YR328
A-AE					0-0	31-62-21	T00508		GRN			D40740P	26			YC051-YD158, YL951-YR328
A-AF					0-0	31-62-21	T00508		BLK			D40740P	27			YC051-YD158, YL951-YR328

WIRE LIST
D280A108

91-21-11
Section W0200
Page 2 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0210	286A0210	E2-1 SHELF (WINDOW HEAT MODULES) LA2													
1001	20	X1	AA	2-7	30-41-11	D40070J	A03				TB5014	REF	=		ALL
1001Z			AA	0-0	30-41-11	D40070J	DED				TB5014	DED			ALL
1002	18	X1	AB	2-1	30-41-11	D40070J	F				TB5010	REF	=		ALL
1002Z			AB	0-0	30-41-11	D40070J	DED				TB5010	DED			ALL
2001B	20	X2	GA	2-0	30-41-11	D01042A	26				D40070J	A08			ALL
2001R	20	X2	GA	0-0	30-41-11	D01042A	13				D40070J	A07			ALL
2001Z			GA	0-0	30-41-11	GD02112	ST..	1F			D40070J	PERG	1F		ALL
2002B	24	Y2	GB	2-9	30-41-11	D01042A	12				TB2101Y	B061	1A		ALL
2002R	24	Y2	GB	0-0	30-41-11	D01042A	19				TB2101Y	A061	1A		ALL
2002Z			GB	0-0	30-41-11	GD02112	ST..	1F			GB02101	ST..	1A		ALL
2003B	20	X2	GC	1-11	30-41-11	D40070J	A06				D01044A	26			ALL
2003R	20	X2	GC	0-0	30-41-11	D40070J	A05				D01044A	13			ALL
2003Z			GC	0-0	30-41-11	D40070J	PERG	1F			GD02106	ST..	1F		ALL
2004B	24	Y2	GD	3-1	30-41-11	TB2101Y	B061	1A			D01044A	12			ALL
2004R	24	Y2	GD	0-0	30-41-11	TB2101Y	A061	1A			D01044A	19			ALL
2004Z			GD	0-0	30-41-11	GB02101	ST..	1A			GD02106	ST..	1F		ALL
2005B	24	Y2	GE	2-11	30-41-11	D40518J	B02				TB2101Y	B061	1A		ALL
2005R	24	Y2	GE	0-0	30-41-11	D40518J	A02				TB2101Y	A061	1A		ALL
2005Z			GE	0-0	30-41-11	D40518J	PERG	1F			GB02101	ST..	1A		ALL
5501	16	CQ		2-2	30-41-11	D41432J	2				D01042B	2			ALL
5502	16	PA		1-8	30-41-11	D01042B	7				GD02105	ST..	1		ALL
5503	16	PA		1-8	30-41-11	D01042B	5				GD02105	AC..	1		ALL
5504	20	PA		1-7	30-41-11	D01042A	6				GD02104	AC..	1A		ALL
5505	24	PK		2-0	30-41-11	D01042A	5				D40518J	A17			ALL
5506	20	PA		1-7	30-41-11	D01042A	10				GD02104	DC..	1A		ALL
5507	24	PK		2-0	30-41-11	D01042A	24				D40518J	B10			ALL
5508	24	PK		2-0	30-41-11	D01042A	25				D40518J	A07			ALL
5509	24	PK		2-0	30-41-11	D01042A	11				D40518J	B07			ALL
5510	12	CQ		2-6	30-41-11	D41432J	1				D01044B	2			ALL
5511	12	HA		1-9	30-41-11	D01044B	7				GD02107	ST..	E		ALL
5512	12	HA		1-9	30-41-11	D01044B	5				GD02108	AC..	E		ALL
5513	20	PA		1-11	30-41-11	D01044A	6				GD02104	AC..	1A		ALL
5514	24	PK		1-10	30-41-11	D40518J	B16				D01044A	5			ALL
5515	20	PA		1-11	30-41-11	D01044A	10				GD02104	DC..	1A		ALL
5516	24	PK		1-10	30-41-11	D40518J	B05				D01044A	24			ALL
5517	24	PK		1-10	30-41-11	D40518J	A06				D01044A	25			ALL
5518	24	PK		1-10	30-41-11	D40518J	B06				D01044A	11			ALL
5519	20	PA		2-4	30-41-11	D01042A	1				TB5014	1	E		ALL
5520	20	PA		2-3	30-41-11	D01042A	7				TB5014	2	E		ALL

WIRE LIST

D280A108

91-21-11

Section W0210

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W0210	286A0210				E2-1 SHELF (WINDOW HEAT MODULES) LA2 (continued)										
5521	20	PA		2-3	30-41-11	D01042A		8			TB5014	3	E		ALL
5522	20	PA		2-4	30-41-11	D01042A		14			TB5014	4	E		ALL
5523	20	PA		2-4	30-41-11	D01042A		20			TB5014	5	E		ALL
5524	20	PA		2-5	30-41-11	D01042A		21			TB5014	6	E		ALL
5525	18	PA		2-1	30-41-11	D01044A		7			TB5010	1	E		ALL
5526	18	PA		2-1	30-41-11	D01044A		8			TB5010	2	E		ALL
5527	18	PA		2-2	30-41-11	D01044A		14			TB5010	3	E		ALL
5528	18	PA		2-2	30-41-11	D01044A		20			TB5010	4	E		ALL
5529	18	PA		2-2	30-41-11	D01044A		21			TB5010	5	E		ALL
5533	22	GA		2-10	23-71-01	D40518J		A11			TB2101X	A057	1A		YC051-YC052
5533	22	PA		2-10	23-71-01	D40518J		A11			TB2101X	A057	1A		YC053-YR328
5534	22	GA		2-10	23-71-01	D40518J		A14			TB2101X	B057	1A		YC051-YC052
5534	22	PA		2-10	23-71-01	D40518J		A14			TB2101X	B057	1A		YC053-YR328
W0212	286A0212				E2-1 SHELF										
0001	22	PA		2-6	21-27-21	D40340J		A01			D40372J	8			YC051-YC059, YC065-YD158
0002	22	PA		1-10	21-27-31	D40934J		A01			D40428J	B01			ALL
0008	22	PA		2-8	29-11-11	D40372J		2			D40718J	A01			ALL
0009	20	CQ		2-2	24-11-11	D40358J		F			D10890B	5			ALL
0010	22	PA		2-4	24-11-11	D40598J		B10			D10890A	61			ALL
0011	18	CQ		3-0	24-11-11	D40428J		F			D40718J	F			ALL
0012	20	CQ		1-9	24-11-11	D10890B		4			GD02103	DC..	1A		ALL
0013	20	PA		1-9	24-11-11	D10890B		1			GD02103	ST..	1A		ALL
0014	22	PA		2-8	24-21-31	D40926J		A04			D10896A	59			ALL
0015	22	PA		2-8	24-21-31	D40926J		B04			D10896A	60			ALL
0016	22	PA		2-8	24-21-31	D40926J		A05			D10896A	8			ALL
0017	22	PA		2-4	24-22-11	D40598J		B04			D10890A	46			ALL
0018	22	PA		2-4	24-22-11	D40598J		A05			D10890A	57			ALL
0019	22	PA		2-3	24-22-11	D10890A		19			D40340J	B03			ALL
0020	22	PA		2-3	24-22-11	D10890A		18			D40340J	B04			ALL
0021	22	PA		2-4	24-22-11	D10890A		20			D40358J	A09			ALL
0022	22	PA		2-2	24-22-11	D10890B		37			D40340J	A03			ALL
0023	22	PA		2-2	24-22-11	D10890B		49			D40340J	B02			ALL
0024	22	PA		2-2	24-22-11	D10890B		29			D40340J	A04			ALL
0025	20	CQ		1-11	24-22-31	D40358J		G			D10896B	5			ALL
0026	22	PA		1-9	24-22-31	D10896B		4			GD02104	DC..	1A		ALL
0027	22	PA		1-9	24-22-31	D10896B		1			GD02104	ST..	1A		ALL
0028	22	PA		1-9	24-22-31	D10896B		36			GD02104	DC..	1A		ALL

WIRE LIST

D280A108

91-21-11
Section W0210
Page 2
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0212		286A0212			E2-1 SHELF (continued)											
0029		22		PA		2-2	24-22-31	D40564J	A01			D40926J	B06			ALL
0030		22		PA		2-8	24-22-31	D40926J	A06			D10896A	18			ALL
0031		22		PA		2-0	24-22-31	D10896A	20			D40358J	B09			ALL
0032		18		PA		2-4	24-22-31	D10896B	3			D40372J	4			ALL
0033		22		PA		1-11	24-22-31	D10896B	38			D40358J	B06			ALL
0034		22		PA		1-11	24-22-31	D10896B	23			D40358J	A02			ALL
0035		22		PA		1-11	24-22-31	D10896B	24			D40358J	B07			ALL
0036		22		PA		1-11	24-22-31	D10896B	37			D40358J	B01			ALL
0037		22		PA		2-2	24-23-11	D10890B	7			D40358J	A05			ALL
0038		22		PA		2-2	24-23-11	D10890B	17			D40358J	A06			ALL
0039		24		PK		1-11	24-28-41	D40358J	A07			D10896B	25			ALL
0040		24		PK		2-2	24-28-41	D40358J	A08			D10890B	25			ALL
0041		24		PK		2-9	24-28-41	D40340J	A05			D40926J	B05			ALL
0050		08		PA		2-3	24-32-11	D00102	7			TB5210	1	E		ALL
0051		08		PA		2-10	24-32-11	D00102	4			GD01256	DC..	P		ALL
0052		18		PA		2-5	24-32-11	D40934J	J			D00102	3			ALL
0053		18		PA		2-5	24-32-11	D40934J	F			D00102	2			ALL
0054		18		PA		2-5	24-32-11	D40934J	G			D00102	1			ALL
0055		18		PA		2-9	24-32-11	GD02105	AC..	1		D00102	6			ALL
0056		20		PA		3-3	24-41-11	D40342J	H			D40340J	H			ALL
0058		22		PA		2-2	49-62-11	D40564J	A02			D40926J	A01			ALL
0059		22		PA		2-2	49-62-11	D40564J	A03			TB2101Y	A001	1A		ALL
0060		22		PA		2-5	49-62-11	D40926J	B01			TB2101Y	A001	1A		ALL
0061		22		PA		2-2	49-62-11	D40564J	A04			D40926J	A02			ALL
0064		22		PA		2-2	49-94-21	D40564J	A05			D40926J	B02			ALL
0065		22		PA		2-2	49-94-21	D40564J	A06			D40926J	A03			ALL
0066		22		PA		3-3	24-22-31	D10896A	11			TB2101Y	A001	1A		ALL
0067		24		PK		2-4	31-62-14	D40926J	A10			D10890A	33			ALL
0068		22		PA		2-2	24-23-11	D10890A	9			GD02104	DC..	1A		ALL
0069		22		PA		0-7	24-22-31	D10896B	6			D10896B	14			ALL
0070		20		PA		2-3	28-23-11	D40342J	A03			D40598J	A06			ALL
0071		20		PA		2-3	28-23-11	D40342J	A04			D40598J	A07			YC051-YD157
0072		20		PA		2-3	28-23-11	D40342J	A05			D40598J	A08			ALL
0073		22		CQ		2-4	28-43-11	D40598J	A04			TB2101Y	A005	1A		YC051-YD157
0074		22		CQ		2-11	28-43-11	D40598J	B05			D40258J	A10			ALL
0075		18		PA		1-11	38-32-12	D40342J	F			D40910J	K			ALL
0076		20		PA		1-11	38-32-12	D40342J	B03			D40910J	B06			ALL
0077		24		PK		2-5	31-62-14	D40926J	B03			TB2101Y	A005	1A		YC051-YD157
0078		22		CQ		3-6	28-43-11	TB2101Y	A005	1A		D40258J	A04			YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0210

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W0212	286A0212				E2-1 SHELF (continued)												
0079	22		PA		2-0	24-22-31		D10896A	29			D40358J	A03			ALL	
0080	20		CQ		2-1	49-62-11		D40564J	B02			TB2101Y	A009	1A		ALL	
0081	20		CQ		1-11	49-62-11		TB2101Y	A009	1A		D40254J	A04			ALL	
0082	20		CQ		1-9	49-62-11		D40564J	B01			D40254J	A02			ALL	
0083	20		CQ		1-11	49-62-11		TB2101Y	A009	1A		D40254J	A03			ALL	
0200	22		PA		2-5	23-71-01		TB2101X	A057	1A		D40428J	A04			ALL	
0201	22		PA		2-5	23-71-01		TB2101X	B057	1A		D40428J	A08			ALL	
0205	20		PA		1-10	28-23-11		D40342J	A04			D40428J	A07			YD158-YR328	
0206	20		PA		1-11	28-23-11		D40598J	A07			D40428J	A03			YD158-YR328	
0207	22		CQ		1-10	28-43-11		D40598J	B07			D40926J	B03			YD158-YR328	
0208	22		CQ		3-6	28-43-11		D40258J	A04			TB2101Y	B011	1A		YD158-YR328	
0209	22		CQ		2-4	28-43-11		D40598J	A04			TB2101Y	B011	1A		YD158-YR328	
0210	22		CQ		1-11	28-43-11		D40428J	B05			TB2101Y	A011	1A		YD158-YR328	
0211	22		CQ		2-10	21-27-21		D40428J	B03			D40340J	A01			YD160-YR328	
0212	22		CQ		2-4	21-27-21		D40428J	A05			D40372J	8			YD160-YR328	
0213	20		PA		1-11	28-23-11		D49996J	A10			D40428J	G			YD160-YR328	
0214	20		PA		1-11	28-23-11		D49996J	B10			D40428J	H			YD160-YR328	
0215	20		PA		1-11	28-23-11		D40598J	A01			D40428J	K			YD160-YR328	
0514	16		PA		1-10	25-51-21		D40254J	F			D40256J	F			YC051-YL999, YR301-YR328	
0515	16		PA		1-10	25-51-21		D40254J	G			D40256J	G			YC051-YL999, YR301-YR328	
0516	16		PA		1-10	25-51-21		D40254J	H			D40256J	H			YC051-YL999, YR301-YR328	
0517	22		PA		1-10	25-51-21		D40254J	A01			D40256J	A01			YC051-YL999, YR301-YR328	
0518	20		PA		2-1	38-41-13		D40260J	A03			D40256J	A03			ALL	
0519	20		PA		2-1	38-41-13		D40260J	B03			D40256J	B03			ALL	
0520	20		PA		2-1	38-41-13		D40260J	A04			D40256J	A04			ALL	
0521	20		PA		2-1	38-41-13		D40260J	B04			D40256J	B04			ALL	
2001B	22		PB	GA	2-4	24-11-11		D10890B	15			D40132J	B03			ALL	
2001R	22		PB	GA	0-0	24-11-11		D10890B	27			D40132J	A03			ALL	
2002B	20		X2	GB	2-4	24-21-11		D10890B	56			D40132J	K			ALL	
2002R	20		X2	GB	0-0	24-21-11		D10890B	55			D40132J	J			ALL	
2002Z				GB	0-0	24-21-11		GD02109	ST..	1A		D40132J	B10			ALL	
2003B	22		X2	GC	2-10	24-21-31		D40910J	B08			D10896B	11			ALL	
2003R	22		X2	GC	0-0	24-21-31		D40910J	A08			D10896B	21			ALL	
2003Z				GC	0-0	24-21-31		D40910J	DED			D10896B	DED			ALL	
2004B	22		PB	GD	2-5	24-22-11		D40428J	B06			D10890A	43			ALL	

WIRE LIST

D280A108

91-21-11

Section W0210

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0212		286A0212				E2-1 SHELF (continued)										
2004R		22		PB	GD	0-0	24-22-11	D40428J	A06			D10890A	55			ALL
2005B		22		PB	GE	2-2	24-22-11	D40358J	B03			D10890B	14			ALL
2005R		22		PB	GE	0-0	24-22-11	D40358J	B02			D10890B	6			ALL
2006B		22		X2	GF	2-10	24-22-31	D40564J	A08			D10896B	62			ALL
2006R		22		X2	GF	0-0	24-22-31	D40564J	A07			D10896B	64			ALL
2006Z					GF	0-0	24-22-31	D40564J	DED			D10896B	DED			ALL
2007B		22		X2	GG	2-9	24-22-31	D40428J	A10			D10896A	55			ALL
2007R		22		X2	GG	0-0	24-22-31	D40428J	B10			D10896A	43			ALL
2007Z					GG	0-0	24-22-31	D40428J	DED			D10896A	DED			ALL
2008B		22		X2	GH	2-11	24-22-31	D40910J	B10			D10896A	10			ALL
2008R		22		X2	GH	0-0	24-22-31	D40910J	A10			D10896A	1			ALL
2008Z					GH	0-0	24-22-31	D40910J	DED			D10896A	DED			ALL
2009B		22		PB	GI	2-0	24-22-31	D40358J	B10			D10896A	56			ALL
2009R		22		PB	GI	0-0	24-22-31	D40358J	A10			D10896A	44			ALL
2010B		22		X2	GJ	2-7	24-23-11	D40910J	B09			D10890A	10			ALL
2010R		22		X2	GJ	0-0	24-23-11	D40910J	A09			D10890A	1			ALL
2010Z					GJ	0-0	24-23-11	D40910J	DED			D10890A	DED			ALL
2011B		22		PB	GK	3-2	24-28-11	TB2101Y	A003	1A		D10896B	60			ALL
2011R		22		PB	GK	0-0	24-28-11	TB2101Y	B001	1A		D10896B	47			ALL
2012B		22		PB	GL	2-2	24-28-11	D40598J	B03			D10890B	60			ALL
2012R		22		PB	GL	0-0	24-28-11	D40598J	A03			D10890B	47			ALL
2014B		24		Y2	GN	2-0	24-33-11	D40428J	A02			D00102	8			ALL
2014R		24		Y2	GN	0-0	24-33-11	D40428J	B02			D00102	5			ALL
2014Z					GN	0-0	24-33-11	D40428J	DED			D00102	DED			ALL
2015B		22		PB	GP	2-5	49-62-11	D40926J	B07			TB2101	CAP	Y		YC051-YC058
2015B		22		PB	GP	2-5	49-62-11	D40926J	B07			TB2101Y	A003	1A		YC059-YR328
2015R		22		PB	GP	0-0	49-62-11	D40926J	A07			TB2101	CAP	Y		YC051-YC058
2015R		22		PB	GP	0-0	49-62-11	D40926J	A07			TB2101Y	B001	1A		YC059-YR328
2016B		22		PB	GQ	2-5	24-28-11	D40598J	B02			TB2101Y	A003	1A		ALL
2016R		22		PB	GQ	0-0	24-28-11	D40598J	A02			TB2101Y	B001	1A		ALL
2201B		22		PB	KA	2-2	49-71-21	D40564J	A10			D40926J	B08			ALL
2201R		22		PB	KA	0-0	49-71-21	D40564J	A09			D40926J	A08			ALL
3001B		18		X3	WA	2-5	24-21-11	D10890A	5			D40132J	G			ALL
3001R		18		X3	WA	0-0	24-21-11	D10890A	3			D40132J	F			ALL
3001Y		18		X3	WA	0-0	24-21-11	D10890A	4			D40132J	H			ALL
3001Z					WA	0-0	24-21-11	GD02109	ST..	1A		D40132J	A10			ALL
3002B		22		PC	WB	2-2	24-22-11	D40598J	B09			D10890B	62			ALL
3002R		22		PC	WB	0-0	24-22-11	D40598J	A09			D10890B	64			ALL
3002Y		22		PC	WB	0-0	24-22-11	D40598J	A10			D10890B	63			ALL

WIRE LIST

D280A108

91-21-11

Section W0210

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0212	286A0212			E2-1 SHELF (continued)											
3003B	20	PC	WC		2-3	24-22-11	D10890A		36		D40340J	B05			ALL
3003R	20	PC	WC		0-0	24-22-11	D10890A		23		D40340J	A06			ALL
3003Y	20	PC	WC		0-0	24-22-11	D10890A		35		D40340J	B06			ALL
3004B	22	X3	WD		2-10	24-22-31	D40564J		B12		D10896B	63			ALL
3004R	22	X3	WD		0-0	24-22-31	D40564J		B11		D10896B	50			ALL
3004Y	22	X3	WD		0-0	24-22-31	D40564J		B13		D10896B	51			ALL
3004Z			WD		0-0	24-22-31	D40564J		DED		D10896B	DED			ALL
3005B	20	PC	WE		2-11	24-22-31	D40910J		B01		D10896A	36			ALL
3005R	20	PC	WE		0-0	24-22-31	D40910J		A01		D10896A	23			ALL
3005Y	20	PC	WE		0-0	24-22-31	D40910J		A02		D10896A	35			ALL
3006B	20	PC	WF		2-2	24-23-11	D40340J		B07		D10890B	53			ALL
3006R	20	PC	WF		0-0	24-23-11	D40340J		A07		D10890B	66			ALL
3006Y	20	PC	WF		0-0	24-23-11	D40340J		A08		D10890B	54			ALL
3201B	20	PC	YA		3-7	28-23-11	D49996J		A03		D40258J	A03			ALL
3201R	20	PC	YA		0-0	28-23-11	D49996J		A01		D40258J	A01			ALL
3201Y	20	PC	YA		0-0	28-23-11	D49996J		A02		D40258J	A02			ALL
3202B	18	PC	YB		3-7	28-23-11	D49996J		H		D40258J	H			ALL
3202R	18	PC	YB		0-0	28-23-11	D49996J		F		D40258J	F			ALL
3202Y	18	PC	YB		0-0	28-23-11	D49996J		G		D40258J	G			ALL
3203B	20	PC	YC		3-7	28-23-11	D49996J		B03		D40258J	B03			ALL
3203R	20	PC	YC		0-0	28-23-11	D49996J		B01		D40258J	B01			ALL
3203Y	20	PC	YC		0-0	28-23-11	D49996J		B02		D40258J	B02			ALL
4001B	20	PD	A6		2-10	24-21-11	D10890A		16		D40342J	B01			ALL
4001G	20	PD	A6		0-0	24-21-11	D10890A		17		D40342J	A02			ALL
4001R	20	PD	A6		0-0	24-21-11	D10890A		7		D40342J	A01			ALL
4001Y	20	PD	A6		0-0	24-21-11	D10890A		15		D40342J	B02			ALL
4002B	20	HD	B6		2-11	24-21-31	D40910J		G		D10896A	16			ALL
4002G	20	HD	B6		0-0	24-21-31	D40910J		J		D10896A	17			ALL
4002R	20	HD	B6		0-0	24-21-31	D40910J		F		D10896A	7			ALL
4002Y	20	HD	B6		0-0	24-21-31	D40910J		H		D10896A	15			ALL
4003B	22	PD	C6		2-5	24-24-11	D40132J		A02		D10890A	54			ALL
4003G	22	PD	C6		0-0	24-24-11	D40132J		A01		D10890A	53			ALL
4003R	22	PD	C6		0-0	24-24-11	D40132J		B02		D10890A	41			ALL
4003Y	22	PD	C6		0-0	24-24-11	D40132J		B01		D10890A	42			ALL
4004B	22	PD	D6		2-3	24-24-11	D40340J		A09		D10890A	51			ALL
4004G	22	PD	D6		0-0	24-24-11	D40340J		B09		D10890A	52			ALL
4004R	22	PD	D6		0-0	24-24-11	D40340J		B08		D10890A	38			ALL
4004Y	22	PD	D6		0-0	24-24-11	D40340J		A10		D10890A	39			ALL
4005B	22	PD	E6		2-11	24-24-31	D40910J		A05		D10896A	51			ALL

WIRE LIST

D280A108

91-21-11

Section W0210

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0212		286A0212			E2-1 SHELF (continued)											
4005G		22		PD	E6	0-0	24-24-31	D40910J	A06			D10896A	52			ALL
4005R		22		PD	E6	0-0	24-24-31	D40910J	B04			D10896A	38			ALL
4005Y		22		PD	E6	0-0	24-24-31	D40910J	B05			D10896A	39			ALL
4006B		20		X4	F6	2-11	24-24-31	D40910J	B02			D10896A	54			ALL
4006G		20		X4	F6	0-0	24-24-31	D40910J	A04			D10896A	53			ALL
4006R		20		X4	F6	0-0	24-24-31	D40910J	A03			D10896A	41			ALL
4006Y		20		X4	F6	0-0	24-24-31	D40910J	B03			D10896A	42			ALL
4006Z					F6	0-0	24-24-31	D40910J	DED			GD02110	ST..	1A		ALL
6001		20		CQ		3-0	28-21-11	D40718J	B08			D40428J	A01			ALL

WIRE LIST

D280A108

91-21-11

Section W0210

Page 7 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0220	286A0220				E2-2 SHELF										
0001	22		PA		2-11	24-21-31	D11114C		29		D40942J	A01			YC051-YD158, YL951-YR328
0002	22		PA		2-11	24-21-31	D11114C		28		D40942J	B01			YC051-YD158, YL951-YR328
0003	22		PA		2-11	24-21-31	D11114C		17		D40942J	A02			YC051-YD158, YL951-YR328
0006	24		B6		2-9	24-31-11	D40360J		17		TB2201Y	A001	1A		YC051-YD158, YL951-YR328
0011	20		PA		1-7	33-32-11	D40380J		B20		D43024J	B04			YC051-YD158, YL951-YR328
0012	20		PA		1-7	33-32-11	D40380J		A20		D43024J	A04			YC051-YD158, YL951-YR328
0013	20		PA		2-3	33-42-11	D40506J		B01		D43060J		2		YC051-YD158, YL951-YR328
0014	20		PA		2-3	33-42-11	D40506J		A02		D43060J		1		YC051-YD158, YL951-YR328
0015	20		PA		2-3	33-42-11	D40506J		A01		D43060J		4		YC051-YD158, YL951-YR328
0016	18		CQ		2-1	33-42-11	D40430J	1	18		D40118J		7		YC051-YD158, YL951-YR328
0017	20		PA		1-9	33-43-11	D40520J		B18		D40118J		2		YC051-YD158, YL951-YR328
0018	20		PA		2-8	23-71-01	D40456J		A08		D41012J	A04			YC051-YD158, YL951-YR328
0019	20		PA		1-10	33-44-11	D40506J			AA	GD02203	ST..	1A		YC051-YD158, YL951-YR328
0020	20		PA		2-8	23-71-01	D40456J		A07		D41012J	A05			YC051-YD158, YL951-YR328
0022	20		PA		2-1	33-44-12	D40506J		B02		TB2201Y	B001	1A		YC051-YD158, YL951-YR328
0023	20		PA		3-4	33-44-12	D40912J		A04		TB2201Y	B001	1A		YC051-YD158, YL951-YR328
0024	20		PA		2-9	33-44-12	D40360J		1		TB2201Y	B001	1A		YC051-YD158, YL951-YR328
0025	20		PA		2-4	33-44-12	D40118J		1		TB2201Y	B001	1A		YC051-YD158, YL951-YR328
0030	16		PA		1-9	33-45-11	D40506J		K		D40118J		4		YC051-YD158, YL951-YL959, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W0220

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0220	286A0220			E2-2 SHELF (continued)											
0030	16		PA		1-10	33-45-11	D40506J		K		D40118J		4		YL963-YL999, YN236-YR328
0031	24		PK		2-6	27-23-14	D40506J		B09		D43008J		A01		YC051-YD158, YL951-YR328
0037	22		PA		2-2	29-11-11	D40506J		B07		D40360J		7		YC051-YD158, YL951-YR328
0046	24		PK		3-3	21-31-11	D40520J		A03		D10738B		B03		YC051-YD158, YL951-YR328
0047	20		PA		2-0	21-31-22	D40520J		A12		TB2201Y		B003	1A	YC051-YD158, YL951-YR328
0048	20		PA		3-0	21-31-22	D40240J		A01		TB2201Y		B003	1A	YC051-YD158, YL951-YR328
0049	24		G6		2-8	21-31-23	D41012J		A08		TB2201Y		B023	1A	YC051-YD158, YL951-YR328
0050	20		PA		3-8	21-31-22	D10738C		3		TB2201Y		B003	1A	YC051-YD158, YL951-YR328
0051	20		PA		2-3	21-31-22	D10738C		2		GD02204		DC..	1A	YC051-YD158, YL951-YR328
0052	20		PA		2-7	21-31-22	D10738C		4		GD02203		ST..	1A	YC051-YD158, YL951-YR328
0053	24		PK		3-3	21-31-22	D40520J		B03		D10738B		B07		YC051-YD158, YL951-YR328
0054	24		PK		3-4	21-31-22	D40520J		A05		D10738A		A13		YC051-YD158, YL951-YR328
0055	24		PK		0-7	21-31-22	TB2201Y		A021	1A	TB2201Y		A023	1A	YC051-YD158, YL951-YR328
0056	24		PK		3-6	21-31-22	D10738A		A11		TB2201Y		B021	1A	YC051-YD158, YL951-YR328
0057	24		PK		1-9	21-31-22	D40520J		A02		TB2201Y		A023	1A	YC051-YD158, YL951-YR328
0058	24		PK		2-4	21-31-22	D10738B		B05		D40240J		A07		YC051-YD158, YL951-YR328
0059	22		PA		2-4	21-31-22	D10738B		C11		GD02204		DC..	1A	YC051-YD158, YL951-YR328
0060	22		GA		2-4	21-31-22	D10738B		B10		GD02204		DC..	1A	YC051-YC052, YC054,
0061	22		PA		2-4	21-31-22	D10738B		A15		GD02204		DC..	1A	YC056-YC059, YC065 YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0220

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0220	286A0220				E2-2 SHELF (continued)										
0062	24		G6		2-3	21-31-24	D40456J	B08			TB2201Y	A005	1A		YC051-YD158, YL951-YR328
0063	24		G6		3-9	21-31-24	D40380J	B04			TB2201Y	A005	1A		YC051-YD158, YL951-YR328
0064	24		PK		3-3	21-31-24	D40450J	A06			TB2201Y	B005	1A		YC051-YD158, YL951-YR328
0065	24		PK		1-10	21-31-24	D40380J	B03			D10738B	B06			YC051-YD158, YL951-YR328
0066	24		PK		1-10	21-31-24	D40380J	B02			D10738B	B02			YC051-YD158, YL951-YR328
0067	24		PK		3-9	21-31-24	D40380J	B05			TB2201Y	B005	1A		YC051-YD158, YL951-YR328
0068	24		PK		2-0	21-31-24	D40380J	B06			D10738A	A15			YC051-YD158, YL951-YR328
0069	24		PK		2-0	21-31-24	D40380J	B07			D10738A	D03			YC051-YD158, YL951-YR328
0070	24		PK		1-10	21-31-24	D40380J	B08			D10738B	B12			YC051-YD158, YL951-YR328
0071	24		PK		1-10	21-31-24	D40380J	B09			D10738B	B13			YC051-YD158, YL951-YR328
0072	24		G6		3-10	21-31-24	D10738B	B01			TB2201Y	A005	1A		YC051-YD158, YL951-YR328
0073	24		PK		3-10	21-31-24	D10738B	B04			TB2201Y	B005	1A		YC051-YD158, YL951-YR328
0074	24		PK		1-10	21-31-24	D10738B	B09			D40380J	B10			YC051-YD158, YL951-YR328
0075	24		PK		3-3	21-42-11	D40456J	B06			D40380J	A01			YC051-YD158, YL951-YR328
0076	24		PK		3-3	21-42-11	D40456J	B07			D40380J	B01			YC051-YD158, YL951-YR328
0077	24		PK		3-3	21-51-14	D40380J	A10			D40456J	B05			YC051-YD158, YL951-YR328
0084	24		PK		3-9	36-11-11	D40380J	A11			TB2201Y	B007	1A		YC051-YD158, YL951-YR328
0085	24		PK		1-11	36-11-11	D40380J	A12			D40130J	A13			YC051-YD158, YL951-YR328
0086	24		PK		1-11	36-11-11	D40380J	A13			D40130J	B13			YC051-YD158, YL951-YR328

WIRE LIST
D280A108

91-21-11
Section W0220
Page 3
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W0220	286A0220				E2-2 SHELF (continued)											
0087	24		PK		1-11	36-11-11	D40380J		A14			D40130J		A14		YC051-YD158, YL951-YR328
0089	24		PK		2-8	36-21-11	D40430J		9			D40246J		A03		YC051-YD158, YL951-YR328
0090	24		PK		1-11	36-21-11	D40520J		A16			D40246J		A04		YC051-YD158, YL951-YL959, YN231-YN235
0090	24		PK		2-0	36-21-11	D40520J		A16			TB2201Y		B033	1A	YL963-YL999, YN236-YR328
0091	24		PK		1-11	36-21-11	D40520J		B16			D40246J		A05		YC051-YD158, YL951-YL959, YN231-YN235
0091	24		PK		2-0	36-21-11	D40520J		B16			TB2201Y		A033	1A	YL963-YL999, YN236-YR328
0092	22		PA		2-8	23-22-11	D40456J		A01			D41012J		A01		YC051-YD158, YL951-YR328
0093	22		PA		2-8	23-22-11	D40456J		A02			D41012J		A02		YC051-YD158, YL951-YR328
0094	22		PA		2-8	23-22-11	D40456J		A03			D41012J		A03		YC051-YD158, YL951-YR328
0099	22		PA		2-6	32-35-11	D40430J		4			D43024J		A03		YC051-YD158, YL951-YR328
0103	22		PA		2-10	49-62-11	D40348J		B03			D40946J		A02		YC051-YD158, YL951-YR328
0105	20		CQ		1-6	49-62-11	D40360J		18			SM00011			9	YC051-YD158, YL951-YR328
0106	22		CQ		1-5	49-62-11	D43050J		B03			SM00011			9	YC051-YD158, YL951-YR328
0107	22		CQ		1-9	49-62-11	D43050J		A04			D40928J		B10		YC051-YD158, YL951-YR328
0109	20		CQ		2-1	49-41-11	D40360J		25			D11114C		55		YC051-YD158, YL951-YR328
0110	20		CQ		2-0	49-41-11	GD02203		AC..	1A		D11114C		56		YC051-YD158, YL951-YR328
0112	20		CQ		2-0	49-41-11	GD02203		DC..	1A		D11114C		4		YC051-YD158, YL951-YR328
0113	24		PK		2-9	49-41-11	D40456J		A06			D11114C		16		YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0220

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0220	286A0220			E2-2 SHELF (continued)											
0114	22		PA		2-11	49-41-11	D11478A	46			D11114C	19			YC051-YD158, YL951-YR328
0115	12		PA		2-2	49-41-11	D11478B	5			D43084J	1			YC051-YD158, YL951-YR328
0116	12		PA		2-2	49-41-11	D11478B	6			D43084J	2			YC051-YD158, YL951-YR328
0117	12		PA		2-2	49-41-11	D11478B	7			D43084J	3			YC051-YD158, YL951-YR328
0118	24		PK		3-2	49-41-11	D11114C	7			TB2201Y	A001	1A		YC051-YD158, YL951-YR328
0119	24		PK		2-11	49-41-11	D11114C	61			D40928J	B03			YC051-YD158, YL951-YR328
0120	24		PK		2-11	49-41-11	D11114C	62			D40928J	A04			YC051-YD158, YL951-YR328
0121	24		PK		2-11	49-41-11	D11114C	63			D40928J	B04			YC051-YD158, YL951-YR328
0122	24		PK		2-0	49-41-11	D40928J	A03			TB2201Y	A001	1A		YC051-YD158, YL951-YR328
0123	24		PK		2-11	49-41-11	D11114C	64			D40928J	A05			YC051-YD158, YL951-YR328
0124	16		PA		1-11	49-41-11	D11114B	20			GD02205	ST..	1		YC051
0124	16		PA		1-10	49-41-11	D11114B	20			GD02205	ST..	1		YC052-YD158, YL951-YR328
0125	16		PA		1-11	49-41-11	D11114B	21			GD02205	ST..	1		YC051
0125	16		PA		1-10	49-41-11	D11114B	21			GD02205	ST..	1		YC052-YD158, YL951-YR328
0126	22		CQ		2-0	49-41-11	D11114C	12			GD02203	AC..	1A		YC051-YD158, YL951-YR328
0130	20		PA		2-8	29-25-11	D40456J	F			D43008J	B03			YC051-YD158, YL951-YR328
0133	24		G6		2-3	29-34-11	D40506J	B06			D43060J	7			YC051-YD158, YL951-YR328
0135	22		PA		2-2	30-11-11	D40520J	A19			D40360J	4			YC051-YD158, YL951-YR328
0136	22		PA		2-2	30-11-11	D40520J	B19			D40360J	5			YC051-YD158, YL951-YR328
0137	22		PA		1-9	30-11-11	D40520J	A20			D40118J	11			YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0220

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0220	286A0220			E2-2 SHELF (continued)											
0138	22		PA		1-9	30-11-11	D40520J	B20			D40118J	12			YC051-YD158, YL951-YR328
0139	24		B6		2-7	31-31-15	D40360J	2			TB2201Y	B011	1A		YC051-YD158, YL951-YR328
0140	24		B6		2-0	31-31-15	D40348J	A01			TB2201Y	A011	1A		YC051-YD158, YL951-YR328
0141	24		B6		2-0	31-31-15	D40348J	B01			TB2201Y	B013	1A		YC051-YD158, YL951-YR328
0205	22		PA		1-11	21-25-11	D40724J	A15			SM00013		9		YL951-YR328
0207	22		CQ		1-9	28-43-11	D40520J	A01			D40118J	3			YC051-YD158, YL951-YR328
0209	22		PA		3-3	32-41-11	D43024J	B03			D43050J	B04			YC051-YD158, YL951-YR328
0210	22		PA		1-11	21-25-11	D40724J	A16			SM00014		9		YL951-YR328
0211	24		PK		0-7	26-16-21	SM00013		9		D40646J	A02			YL951-YR328
0212	24		PK		3-3	73-22-31	D40380J	B11			D40456J	B09			YC051-YD158, YL951-YR328
0213	24		B6		1-9	76-21-11	D40348J	A14			D40136J	A03			YC051-YD158, YL951-YR328
0214	24		B6		1-9	76-21-11	D40348J	B14			D40136J	B03			YC051-YD158, YL951-YR328
0215	20		CQ		1-9	76-21-11	D40348J	A15			D40136J	A05			YC051-YD158, YL951-YR328
0216	24		B6		2-9	80-11-11	D40348J	A07			D40450J	A01			YC051-YD158, YL951-YR328
0217	24		B6		3-3	80-11-11	D40450J	B01			TB2201Y	B007	1A		YC051-YD158, YL951-YR328
0218	24		B6		2-0	80-11-11	D40136J	B04			TB2201Y	B007	1A		YC051-YD158, YL951-YR328
0219	20		CQ		1-10	80-11-11	D40136J	A04			TB2201Y	A009	1A		YC051-YD158, YL951-YR328
0220	20		CQ		2-0	80-11-11	D40348J	B07			TB2201Y	A009	1A		YC051-YD158, YL951-YR328
0221	24		PK		3-3	49-52-31	D40912J	B07			TB2201Y	A009	1A		YC051-YD158, YL951-YR328
0222	24		PK		0-7	26-16-22	SM00014		9		D40646J	B10			YL951-YR328
0227	22		PA		2-11	49-41-11	D11478A	47			D11114C	47			YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0220

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0220	286A0220			E2-2 SHELF (continued)											
0228	24		PK		2-0	31-62-14	D40724J	A07			D40912J	B04			YC051-YD158, YL951-YR328
0230	20		PA		2-8	30-71-11	D40430J	28			D40586J	A03			YC051-YD158, YL951-YR328
0231	20		PA		2-8	30-71-11	D40430J	29			D40586J	B03			YC051-YD158, YL951-YR328
0233	22		CQ		2-4	49-62-11	D01000	6			D40946J	A01			YC051-YD158, YL951-YR328
0236	18		PA		2-8	38-32-12	D40946J	K			D43084J	5			YC051-YD158, YL951-YR328
0237	20		PA		2-8	38-32-12	D40946J	B10			D43084J	4			YC051-YD158, YL951-YR328
0238	22		PA		2-4	21-31-22	D10738B	D08			GD02204	DC..	1A		YC051-YD158, YL951-YR328
0239	22		GA		2-4	21-31-22	D10738B	D07			GD02204	DC..	1A		YC051-YC052, YC054, YC056-YC059, YC065
0240	24		PK		2-0	31-62-14	D40912J	A07			D40724J	A01			YC051-YD158, YL951-YR328
0241	20		PA		1-11	30-71-11	D40456J	B01			TB2201Y	A025	1A		YC051-YD158, YL951-YR328
0242	20		PA		3-3	30-71-11	D40380J	A19			TB2201Y	A025	1A		YC051-YD158, YL951-YR328
0243	20		PA		3-3	30-71-11	D40380J	B19			TB2201Y	A025	1A		YC051-YD158, YL951-YR328
0244	20		PA		2-2	30-71-11	D40586J	B01			TB2201Y	A025	1A		YC051-YD158, YL951-YR328
0245	20		CQ		1-9	49-41-11	D11114C	3			D40946J	A05			YC051-YD158, YL951-YR328
0246	20		CQ		2-5	49-62-11	D40724J	A17			SM00011		9		YC051-YD158, YL951-YR328
0250	20		PA		2-8	30-71-11	D40430J	30			D40586J	B02			YC051-YD158, YL951-YR328
0257	22		PA		1-9	26-16-21	D40506J	A04			TB2201Y	A027	1A		YC053-YD158, YL951-YR328
0258	22		PA		3-7	26-16-21	TB2201Y	A027	1A		D40646J	A09			YC053-YD158, YL951-YR328
0259	22		PA		3-5	26-16-21	TB2201Y	A027	1A		D42014J	A06			YC053-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0220

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0220	286A0220			E2-2 SHELF (continued)											
0260	22		G5		1-9	26-16-21	D40506J	B04			TB2201Y	B027	1A		YC053-YD158, YL951-YR328
0261	22		G5		3-7	26-16-21	TB2201Y	B027	1A		D40646J	A08			YC053-YD158, YL951-YR328
0262	22		G5		3-5	26-16-21	TB2201Y	B027	1A		D42014J	A07			YC053-YD158, YL951-YR328
0263	22		PA		1-9	26-16-21	D40646J	A10			D42014J	A08			YC053-YD158, YL951-YR328
0264	22		G5		1-9	26-16-21	D40646J	B01			D42014J	A09			YC053-YD158, YL951-YR328
0265	22		PA		1-9	26-16-21	D40646J	B02			D42014J	A10			YC053-YD158, YL951-YR328
0266	22		PA		1-9	26-16-21	D40646J	B03			D42014J	B05			YC053-YD158, YL951-YR328
0267	22		PA		1-9	26-16-21	D40646J	B04			D42014J	B06			YC053-YD158, YL951-YR328
0268	22		PA		1-9	26-16-21	D40646J	B05			D42014J	B07			YC053-YD158, YL951-YR328
0269	22		G5		1-9	26-16-21	D40646J	B06			D42014J	B08			YC053-YD158, YL951-YR328
0270	22		G5		2-1	26-16-22	D40506J	A06			TB2201Y	A029	1A		YC053-YD158, YL951-YR328
0271	22		G5		3-3	26-16-22	TB2201Y	A029	1A		D46022J	A06			YC053-YD158, YL951-YR328
0272	22		G5		3-1	26-16-22	TB2201Y	A029	1A		D41840J	A06			YC053-YD158, YL951-YR328
0273	22		G5		2-1	26-16-22	D40506J	A07			TB2201Y	B029	1A		YC053-YD158, YL951-YR328
0274	22		G5		3-3	26-16-22	TB2201Y	B029	1A		D46022J	A05			YC053-YD158, YL951-YR328
0275	22		G5		3-1	26-16-22	TB2201Y	B029	1A		D41840J	A07			YC053-YD158, YL951-YR328
0276	22		G5		1-7	26-16-22	D46022J	A07			D41840J	A08			YC053-YD158, YL951-YR328
0277	22		G5		1-7	26-16-22	D46022J	A08			D41840J	A09			YC053-YD158, YL951-YR328
0278	22		G5		1-7	26-16-22	D46022J	A09			D41840J	A10			YC053-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0220

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0220	286A0220				E2-2 SHELF (continued)										
0279	22		G5		1-7	26-16-22	D46022J	A10			D41840J	B05			YC053-YD158, YL951-YR328
0280	22		G5		1-7	26-16-22	D46022J	B05			D41840J	B06			YC053-YD158, YL951-YR328
0281	22		G5		1-7	26-16-22	D46022J	B06			D41840J	B07			YC053-YD158, YL951-YR328
0282	22		G5		1-7	26-16-22	D46022J	B07			D41840J	B08			YC053-YD158, YL951-YR328
0283	22		CQ		2-1	26-23-11	D40506J	A08			TB2201Y	A031	1A		YC053-YD157, YL951-YR314, YR317-YR318, YR320-YR328
0284	22		CQ		3-4	26-23-11	TB2201Y	A031	1A		D40646J	A06			YC053-YD157, YL951-YR314, YR317-YR318, YR320-YR328
0285	22		CQ		3-4	26-23-11	TB2201Y	A031	1A		D40646J	A07			YC053-YD157, YL951-YR314, YR317-YR318, YR320-YR328
0286	22		PA		1-8	26-23-11	D40646J	A01			D41840J	A05			YC053-YD157, YL951-YR314, YR317-YR318, YR320-YR328
0287	22		CQ		1-8	26-23-11	D40646J	A03			D41840J	A03			YC053-YD157, YL951-YR314, YR317-YR318, YR320-YR328
0288	22		CQ		1-8	26-23-11	D40646J	A05			D41840J	A01			YC053-YD157, YL951-YR314, YR317-YR318, YR320-YR328
0289	22		CQ		3-5	26-23-11	D40646J	A06			D40506J	A08			YD158
0289	22		CQ		3-5	26-23-11	D40506J	A08			D40646J	A06			YR315-YR316, YR319
0290	22		CQ		3-5	26-23-11	D40646J	A05			D40506J	A09			YD158
0290	22		CQ		3-5	26-23-11	D40506J	A09			D40646J	A05			YR315-YR316, YR319
0291	22		PA		3-4	26-23-11	D40646J	A07			TB2201Y	B031	1A		YD158, YR315-YR316, YR319
0292	22		PA		3-2	26-23-11	D42014J	A05			TB2201Y	B031	1A		YD158

WIRE LIST

D280A108

91-21-11

Section W0220

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0220	286A0220			E2-2 SHELF (continued)											
0292	22		PA		3-2	26-23-11	TB2201Y	B031	1A		D42014J	A05			YR315-YR316, YR319
0293	22		PA		3-1	26-23-11	D41840J	A05			TB2201Y	B031	1A		YD158
0293	22		PA		3-1	26-23-11	TB2201Y	B031	1A		D41840J	A05			YR315-YR316, YR319
0294	22		CQ		1-8	26-23-11	D46022J	A01			D42014J	A01			YD158, YR315-YR316, YR319
0295	22		CQ		1-8	26-23-11	D46022J	A03			D42014J	A03			YD158, YR315-YR316, YR319
0296	22		CQ		1-8	26-23-11	D40646J	A01			D41840J	A03			YD158, YR315-YR316, YR319
0297	22		CQ		1-8	26-23-11	D40646J	A03			D41840J	A01			YD158, YR315-YR316, YR319
0303	24		PK		3-6	31-31-15	D40348J	A10			D40646J	A02			YC053-YD158
0303	24		PK		3-6	26-16-21	D40348J	A10			SM00013		9		YL951-YR328
0304	24		PK		3-6	31-31-15	D40348J	B10			D40646J	B10			YC053-YD158
0304	24		PK		3-6	26-16-22	D40348J	B10			SM00014		9		YL951-YR328
0305	24		PK		2-5	36-21-11	TB2201Y	B033	1A		D40246J	A04			YL963-YL999, YN236-YR328
0306	24		PK		2-5	36-21-11	TB2201Y	A033	1A		D40246J	A05			YL963-YL999, YN236-YR328
0307	24		PK		2-1	31-35-05	TB2201Y	B033	1A		D40348J	A05			YL963-YL999, YN236-YR328
0308	24		PK		2-1	31-35-05	TB2201Y	A033	1A		D40348J	B05			YL963-YL999, YN236-YR328
0314	24		GK		4-0	21-31-22	D40456J	A04			D10738B	B10			YC053, YC055, YC060-YC064
0314	24		PK		3-4	21-31-22	D40456J	A04			D10738B	B10			YC067-YD158, YL951-YR328
0315	24		GK		4-0	21-31-22	D40456J	B04			D10738B	D07			YC053, YC055, YC060-YC064
0315	24		PK		3-4	21-31-22	D40456J	B04			D10738B	D07			YC067-YD158, YL951-YR328
0316	20		GA		4-0	21-31-22	D40456J	A10			TB2201Y	B003	1A		YC053, YC055
0316	20		GA		3-0	21-31-22	D40456J	A10			TB2201Y	B003	1A		YC060-YC064
0316	20		PA		2-2	21-31-22	D40456J	A10			TB2201Y	B003	1A		YC067-YD158, YL951-YR328
0317	22		GA		4-0	26-16-21	D40646J	B07			TB2201Y	B035	1A		YC053, YC055, YC060-YC064
0317	22		PA		3-3	26-16-21	D40646J	B07			TB2201Y	B035	1A		YC067-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0220

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W0220	286A0220				E2-2 SHELF (continued)											
0318	22		GA		4-0	26-16-21	D40456J		A05			TB2201Y	B035	1A		YC053, YC055
0318	22		GA		3-0	26-16-21	D40456J		A05			TB2201Y	B035	1A		YC060-YC064
0318	22		PA		2-2	26-16-21	D40456J		A05			TB2201Y	B035	1A		YC067-YD158, YL951-YR328
0326	22		PA		2-1	30-31-12	D40506J		B05			TB2201Y	A039	1A		YL968-YL999, YN236-YR328
0327	22		PA		0-7	30-31-12	TB2201Y		A039	1A		TB2201Y	A037	1A		YL968-YL999, YN236-YR328
0328	22		PA		2-7	30-31-12	TB2201Y		B037	1A		D40450J	B05			YL968-YL999, YN236-YR328
0329	22		PA		2-7	30-31-12	TB2201Y		B039	1A		D40450J	A05			YL968-YL999, YN236-YR328
0504	06		CQ		4-0	24-21-31	D11114A		1			TB2202	1	E		YC051
0504	06		CQ		3-1	24-21-31	D11114A		1			TB2202	1	E		YC052-YD158, YL951-YR328
0506	06		CQ		4-0	24-21-31	D11114A		2			TB2202	2	E		YC051
0506	06		CQ		3-1	24-21-31	D11114A		2			TB2202	2	E		YC052-YD158, YL951-YR328
0508	06		CQ		4-0	24-21-31	D11114A		3			TB2202	3	E		YC051
0508	06		CQ		3-1	24-21-31	D11114A		3			TB2202	3	E		YC052-YD158, YL951-YR328
1001	20		X1	AA	1-11	33-44-11	D40506J		A03			D40246J	A07			YC051-YD158, YL951-YR328
1001Z				AA	0-0	33-44-11	D40506J			AA		D40246J	PERG	1F		YC051-YD158, YL951-YR328
1002	20		X1	AB	2-5	21-31-22	D40520J		A06			D40240J	A02			YC051-YD158, YL951-YR328
1002Z				AB	0-0	21-31-22	D40520J		PERG	1F		D40240J	PERG	1F		YC051-YD158, YL951-YR328
1003	22		X1	AC	3-4	21-31-22	D40520J		B06			D10738A	D15			YC051-YD158, YL951-YR328
1003Z				AC	0-0	21-31-22	D40520J		PERG	1F		D10738A	PERG	1A		YC051-YD158, YL951-YR328
1004	20		HE	AD	2-5	73-22-11	D40430J		2			D40138J	A07			YC051-YD158, YL951-YR328
1004Z				AD	0-0	73-22-11	D40430J		6			D40138J	PERG	1F		YC051-YD158, YL951-YR328
1005	20		X1	AE	2-5	74-11-11	D40430J		3			D40138J	A01			YC051-YD158, YL951-YR328

WIRE LIST
D280A108

91-21-11
Section W0220
Page 11
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0220	286A0220			E2-2 SHELF (continued)											
1005Z				AE	0-0	74-11-11	D40430J	5			D40138J	PERG	1F		YC051-YD158, YL951-YR328
1006R	20	X5		AF	2-0	26-21-11	D40912J	A01			D40724J	A19			YC051-YD158, YL951-YR328
1006Z				AF	0-0	26-21-11	D40912J	DED			D40724J	DED			YC051-YD158, YL951-YR328
1007R	20	X5		AG	2-0	26-21-11	D40912J	B01			D40724J	A18			YC051-YD158, YL951-YR328
1007Z				AG	0-0	26-21-11	D40912J	DED			D40724J	DED			YC051-YD158, YL951-YR328
1008R	20	X5		AH	2-1	26-21-11	D40724J	A20			D40012J	A01			YC051-YD158, YL951-YR328
1008Z				AH	0-0	26-21-11	D40724J	DED			D40012J	DED			YC051-YD158, YL951-YR328
1009R	20	X5		AI	3-4	26-21-11	D40724J	B18			D40656J	B01			YC051-YD158, YL951-YR328
1009Z				AI	0-0	26-21-11	D40724J	DED			D40656J	DED			YC051-YD158, YL951-YR328
1010R	20	X5		AJ	3-4	26-21-11	D40724J	B19			D40656J	A02			YC051-YD158, YL951-YR328
1010Z				AJ	0-0	26-21-11	D40724J	DED			D40656J	DED			YC051-YD158, YL951-YR328
1011R	20	X5		AK	3-4	26-21-11	D40724J	B20			D40656J	A03			YC051-YD158, YL951-YR328
1011Z				AK	0-0	26-21-11	D40724J	DED			D40656J	DED			YC051-YD158, YL951-YR328
1012R	20	X5		AL	2-0	26-21-11	D40430J	22			D40012J	B01			YC051-YD158, YL951-YR328
1012Z				AL	0-0	26-21-11	D40430J	DED			D40012J	DED			YC051-YD158, YL951-YR328
1013R	20	X5		AM	2-0	26-21-11	D40430J	18			D40012J	A02			YC051-YD158, YL951-YR328
1013Z				AM	0-0	26-21-11	D40430J	DED			D40012J	DED			YC051-YD158, YL951-YR328
1014R	20	X5		AN	2-0	26-21-11	D40430J	19			D40012J	B02			YC051-YD158, YL951-YR328
1014Z				AN	0-0	26-21-11	D40430J	DED			D40012J	DED			YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0220

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0220	286A0220				E2-2 SHELF (continued)										
1015R	20	X5		AP	2-7	26-21-11	D40430J	17			D40656J	A01			YC051-YD158, YL951-YR328
1015Z				AP	0-0	26-21-11	D40430J	DED			D40656J	DED			YC051-YD158, YL951-YR328
1016R	20	X5		AQ	2-7	26-21-11	D40430J	21			D40656J	B02			YC051-YD158, YL951-YR328
1016Z				AQ	0-0	26-21-11	D40430J	DED			D40656J	DED			YC051-YD158, YL951-YR328
1017R	20	X5		AR	2-7	26-21-11	D40430J	20			D40656J	B03			YC051-YD158, YL951-YR328
1017Z				AR	0-0	26-21-11	D40430J	DED			D40656J	DED			YC051-YD158, YL951-YR328
1018R	22	X5		AS	3-9	26-11-11	D01002	11			TB2201Y	A011	1A		YC051-YD158, YL951-YR328
1018Z				AS	0-0	26-11-11	D01002	DED			TB2201Y	DED			YC051-YD158, YL951-YR328
1019R	22	X5		AT	2-8	26-11-11	D40430J	15			TB2201Y	A011	1A		YC051-YD158, YL951-YR328
1019Z				AT	0-0	26-11-11	D40430J	DED			TB2201Y	DED			YC051-YD158, YL951-YR328
1020R	22	X5		AU	2-11	26-11-11	D01002	15			D40430J	14			YC051-YD158, YL951-YR328
1020Z				AU	0-0	26-11-11	D01002	DED			D40430J	DED			YC051-YD158, YL951-YR328
1021R	22	X5		AV	2-11	26-11-11	D01002	7			D40430J	13			YC051-YD158, YL951-YR328
1021Z				AV	0-0	26-11-11	D01002	DED			D40430J	DED			YC051-YD158, YL951-YR328
1022R	22	X5		AW	2-11	26-11-11	D01002	5			D40430J	12			YC051-YD158, YL951-YR328
1022Z				AW	0-0	26-11-11	D01002	DED			D40430J	DED			YC051-YD158, YL951-YR328
1023R	22	X5		AX	2-11	26-11-11	D01002	8			D40430J	11			YC051-YD158, YL951-YR328
1023Z				AX	0-0	26-11-11	D01002	DED			D40430J	DED			YC051-YD158, YL951-YR328
1024R	22	X5		AY	2-11	26-11-11	D01002	6			D40430J	10			YC051-YD158, YL951-YR328

WIRE LIST
D280A108

91-21-11
Section W0220
Page 13
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W0220	286A0220			E2-2 SHELF (continued)											
1024Z				AY	0-0	26-11-11	D01002	DED			D40430J	DED			YC051-YD158, YL951-YR328
1025R	22	X5	AZ		2-11	26-11-11	D01002	1			D40430J	16			YC051-YD158, YL951-YR328
1025Z				AZ	0-0	26-11-11	D01002	DED			D40430J	DED			YC051-YD158, YL951-YR328
1026R	20	X5	BA		2-6	26-11-11	D01002	2			GD02204	DC..	1A		YC051-YD158, YL951-YR328
1026Z				BA	0-0	26-11-11	D01002	DED			GD02204	DED			YC051-YD158, YL951-YR328
1027R	20	X5	BB		2-6	26-11-11	D01002	22			GD02204	DC..	1A		YC051-YD158, YL951-YR328
1027Z				BB	0-0	26-11-11	D01002	DED			GD02204	DED			YC051-YD158, YL951-YR328
1028R	20	X5	BC		1-11	26-11-11	D01002	24			D40126J	A09			YC051-YD158, YL951-YR328
1028Z				BC	0-0	26-11-11	D01002	DED			D40126J	DED			YC051-YD158, YL951-YR328
1029R	20	X5	BD		1-11	26-11-11	D01002	25			D40126J	B09			YC051-YD158, YL951-YR328
1029Z				BD	0-0	26-11-11	D01002	DED			D40126J	DED			YC051-YD158, YL951-YR328
1030R	20	X5	BE		3-7	26-11-11	D01002	12			D40138J	A04			YC051-YD158, YL951-YR328
1030Z				BE	0-0	26-11-11	D01002	DED			D40138J	DED			YC051-YD158, YL951-YR328
1031R	20	X5	BF		3-7	26-11-11	D01002	10			D40138J	B04			YC051-YD158, YL951-YR328
1031Z				BF	0-0	26-11-11	D01002	DED			D40138J	DED			YC051-YD158, YL951-YR328
1032R	22	X5	BG		3-7	26-11-21	D40348J	A18			D00998	1			YC051-YD158, YL951-YR328
1032Z				BG	0-0	26-11-21	D40348J	DED			D00998	DED			YC051-YD158, YL951-YR328
1033R	20	X5	BH		2-7	26-11-21	D00998	2			GD02204	DC..	1A		YC051-YD158, YL951-YR328
1033Z				BH	0-0	26-11-21	D00998	DED			GD02204	DED			YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0220

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0220	286A0220				E2-2 SHELF (continued)										
1034R	22	X5		BI	2-0	26-11-21	D40348J	A12			TB2201Y	A013	1A		YC051-YD158, YL951-YR328
1034Z				BI	0-0	26-11-21	D40348J	DED			TB2201Y	DED			YC051-YD158, YL951-YR328
1035R	22	X5		BJ	3-11	26-11-21	D00998	13			TB2201Y	A013	1A		YC051-YD158, YL951-YR328
1035Z				BJ	0-0	26-11-21	D00998	DED			TB2201Y	DED			YC051-YD158, YL951-YR328
1036R	20	X5		BK	2-7	26-11-21	D00998	22			GD02204	DC..	1A		YC051-YD158, YL951-YR328
1036Z				BK	0-0	26-11-21	D00998	DED			GD02204	DED			YC051-YD158, YL951-YR328
1037R	22	X5		BL	3-7	26-11-21	D40348J	B12			D00998	4			YC051-YD158, YL951-YR328
1037Z				BL	0-0	26-11-21	D40348J	DED			D00998	DED			YC051-YD158, YL951-YR328
1038R	22	N9		BM	3-5	26-11-21	D40348J	B19			D01002	21			YC051-YC052
1038Z				BM	0-0	26-11-21	D40348J	DED			D01002	DED			YC051-YC052
1101R	20	X5		BN	2-0	26-12-11	D40348J	A09			TB2201Y	A015	1A		YC051-YD158, YL951-YR328
1101Z				BN	0-0	26-12-11	D40348J	DED			TB2201Y	DED			YC051-YD158, YL951-YR328
1102R	22	X5		BP	3-0	26-11-21	D40430J	26			D01000	18			YC051-YD158, YL951-YR328
1102Z				BP	0-0	26-11-21	D40430J	DED			D01000	DED			YC051-YD158, YL951-YR328
1103R	22	N9		BQ	3-7	26-11-21	D40348J	A20			D00998	21			YC051-YC052
1103Z				BQ	0-0	26-11-21	D40348J	DED			D00998	DED			YC051-YC052
1104R	22	X5		BR	3-7	26-11-21	D40348J	B15			D00998	6			YC051-YD158, YL951-YR328
1104Z				BR	0-0	26-11-21	D40348J	DED			D00998	DED			YC051-YD158, YL951-YR328
1105R	22	X5		BS	3-7	26-11-21	D40348J	A16			D00998	8			YC051-YD158, YL951-YR328
1105Z				BS	0-0	26-11-21	D40348J	DED			D00998	DED			YC051-YD158, YL951-YR328
1106R	22	X5		BT	3-7	26-11-21	D40348J	B16			D00998	5			YC051-YD158, YL951-YR328

WIRE LIST
D280A108

91-21-11
Section W0220
Page 15
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W0220	286A0220			E2-2 SHELF (continued)											
1106Z				BT	0-0	26-11-21	D40348J	DED			D00998	DED			YC051-YD158, YL951-YR328
1107R	22	X5	BU		3-7	26-11-21	D40348J	A17			D00998	7			YC051-YD158, YL951-YR328
1107Z				BU	0-0	26-11-21	D40348J	DED			D00998	DED			YC051-YD158, YL951-YR328
1108R	22	X5	BV		2-0	26-11-21	D40348J	B17			TB2201Y	B011	1A		YC051-YD158, YL951-YR328
1108Z				BV	0-0	26-11-21	D40348J	DED			TB2201Y	DED			YC051-YD158, YL951-YR328
1109R	22	X5	BW		3-11	26-11-21	D00998	11			TB2201Y	B011	1A		YC051-YD158, YL951-YR328
1109Z				BW	0-0	26-11-21	D00998	DED			TB2201Y	DED			YC051-YD158, YL951-YR328
1110R	20	X5	BX		2-1	26-11-21	D40380J	B12			D00998	10			YC051-YD158, YL951-YR328
1110Z				BX	0-0	26-11-21	D40380J	DED			D00998	DED			YC051-YD158, YL951-YR328
1111R	20	X5	BY		2-1	26-11-21	D40380J	B13			D00998	12			YC051-YD158, YL951-YR328
1111Z				BY	0-0	26-11-21	D40380J	DED			D00998	DED			YC051-YD158, YL951-YR328
1112R	20	X5	BZ		2-8	26-11-21	D41012J	A06			D00998	25			YC051-YD158, YL951-YR328
1112Z				BZ	0-0	26-11-21	D41012J	DED			D00998	DED			YC051-YD158, YL951-YR328
1113R	20	X5	CA		2-8	26-11-21	D41012J	A07			D00998	24			YC051-YD158, YL951-YR328
1113Z				CA	0-0	26-11-21	D41012J	DED			D00998	DED			YC051-YD158, YL951-YR328
1114R	20	X5	CB		2-11	26-11-31	D01000	1			D40360J	15			YC051-YD158, YL951-YR328
1114Z				CB	0-0	26-11-31	D01000	DED			D40360J	DED			YC051-YD158, YL951-YR328
1115R	22	X5	CC		3-0	26-11-31	D01000	4			D40430J	25			YC051-YD158, YL951-YR328
1115Z				CC	0-0	26-11-31	D01000	DED			D40430J	DED			YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0220

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0220	286A0220				E2-2 SHELF (continued)										
1116R	22	X5	CD		3-10	26-11-31	D01000	11			TB2201Y	B013	1A		YC051-YD158, YL951-YR328
1116Z			CD		0-0	26-11-31	D01000	DED			TB2201Y	DED			YC051-YD158, YL951-YR328
1117R	22	X5	CE		2-8	26-11-31	D40430J	24			TB2201Y	B013	1A		YC051-YD158, YL951-YR328
1117Z			CE		0-0	26-11-31	D40430J	DED			TB2201Y	DED			YC051-YD158, YL951-YR328
1118R	22	N9	CF		2-8	26-11-31	D40430J	23			TB2201Y	A015	1A		YC051-YC052
1118Z			CF		0-0	26-11-31	D40430J	DED			TB2201Y	DED			YC051-YC052
1119R	20	X5	CG		1-10	26-11-31	D43050J	A01			TB2201Y	A015	1A		YC051-YD158, YL951-YR328
1119Z			CG		0-0	26-11-31	D43050J	DED			TB2201Y	DED			YC051-YD158, YL951-YR328
1120R	20	X5	CH		3-9	26-11-31	D01002	13			TB2201Y	A015	1A		YC051-YD158, YL951-YR328
1120Z			CH		0-0	26-11-31	D01002	DED			TB2201Y	DED			YC051-YD158, YL951-YR328
1121R	20	X5	CI		1-10	26-11-31	D43050J	B01			TB2201Y	A013	1A		YC051-YD158, YL951-YR328
1121Z			CI		0-0	26-11-31	D43050J	DED			TB2201Y	DED			YC051-YD158, YL951-YR328
1122R	20	X5	CJ		3-8	26-11-31	D01000	13			D43050J	A02			YC051-YD158, YL951-YR328
1122Z			CJ		0-0	26-11-31	D01000	DED			D43050J	DED			YC051-YD158, YL951-YR328
1123R	20	X5	CK		3-8	26-11-31	D01000	21			D43050J	B02			YC051-YD158, YL951-YR328
1123Z			CK		0-0	26-11-31	D01000	DED			D43050J	DED			YC051-YD158, YL951-YR328
1124R	20	X5	CL		1-11	26-11-31	D43050J	A03			D40456J	H			YC051-YD158, YL951-YR328
1124Z			CL		0-0	26-11-31	D43050J	DED			D40456J	DED			YC051-YD158, YL951-YR328
1125R	20	X5	CM		2-6	26-11-31	D01000	9			GD02204	DC..	1A		YC051-YD158, YL951-YR328
1125Z			CM		0-0	26-11-31	D01000	DED			GD02204	DED			YC051-YD158, YL951-YR328

WIRE LIST
D280A108

91-21-11
Section W0220
Page 17
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0220	286A0220			E2-2 SHELF (continued)											
1126R	20	X5		CN	2-6	26-11-31	D01000		2		GD02204	DC..	1A		YC051-YD158, YL951-YR328
1126Z				CN	0-0	26-11-31	D01000		DED		GD02204	DED			YC051-YD158, YL951-YR328
1127R	20	X5		CP	2-6	26-11-31	D01000		3		GD02204	DC..	1A		YC051-YD158, YL951-YR328
1127Z				CP	0-0	26-11-31	D01000		DED		GD02204	DED			YC051-YD158, YL951-YR328
1128R	20	X5		CQ	2-6	26-11-31	D01000		22		GD02204	DC..	1A		YC051-YD158, YL951-YR328
1128Z				CQ	0-0	26-11-31	D01000		DED		GD02204	DED			YC051-YD158, YL951-YR328
1129R	20	X5		CR	3-9	26-11-31	D01000		25		D40928J	A02			YC051-YD158, YL951-YR328
1129Z				CR	0-0	26-11-31	D01000		DED		D40928J	DED			YC051-YD158, YL951-YR328
1130R	20	X5		CS	3-9	26-11-31	D01000		20		D40928J	B02			YC051-YD158, YL951-YR328
1130Z				CS	0-0	26-11-31	D01000		DED		D40928J	DED			YC051-YD158, YL951-YR328
1131R	20	X5		CT	1-11	26-12-11	D40348J		B18		D40586J	A10			YC051-YD158, YL951-YR328
1131Z				CT	0-0	26-12-11	D40348J		DED		D40586J	DED			YC051-YD158, YL951-YR328
1132R	20	X5		CU	1-11	26-12-11	D40348J		A19		D40586J	B10			YC051-YD158, YL951-YR328
1132Z				CU	0-0	26-12-11	D40348J		DED		D40586J	DED			YC051-YD158, YL951-YR328
1201R	22	N9		DA	2-1	26-11-21	D40348J		B19		TB2201Y	A035	1A		YC053, YC055, YC060-YC064
1201R	22	N9		DA	2-1	26-11-21	D40348J		B19		TB2201Y	A003	1A		YC054, YC056-YC059, YC065
1201R	22	X5		DA	2-1	26-11-21	D40348J		B19		TB2201Y	A035	1A		YC067-YD158, YL951-YR328
1201Z				DA	0-0	26-11-21	D40348J		DED		TB2201Y	DED			YC053-YD158, YL951-YR328
1202R	22	N9		DB	3-11	26-11-21	TB2201Y	A035	1A		D01002		21		YC053, YC055, YC060-YC064

WIRE LIST

D280A108

91-21-11

Section W0220

Page 18

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0220	286A0220				E2-2 SHELF (continued)										
1202R	22	N9	DB		3-11	26-11-21	TB2201Y	A003	1A		D01002	21			YC054, YC056-YC059, YC065
1202R	22	X5	DB		3-3	26-11-21	TB2201Y	A035	1A		D01002	21			YC067-YD158, YL951-YR328
1202Z			DB		0-0	26-11-21	TB2201Y	DED			D01002	DED			YC053-YD158, YL951-YR328
1203R	22	N9	DC		3-11	26-11-21	TB2201Y	A003	1A		D40646J	B07			YC054, YC056-YC059, YC065
1203Z			DC		0-0	26-11-21	TB2201Y	DED			D40646J	DED			YC054, YC056-YC059, YC065
1204R	22	X5	DD		2-0	26-11-21	D40348J	A20			TB2201Y	B009	1A		YC053-YD158, YL951-YR328
1204Z			DD		0-0	26-11-21	D40348J	DED			TB2201Y	DED			YC053-YD158, YL951-YR328
1205R	22	X5	DE		3-11	26-11-21	TB2201Y	B009	1A		D00998	21			YC053-YD158, YL951-YR328
1205Z			DE		0-0	26-11-21	TB2201Y	DED			D00998	DED			YC053-YD158, YL951-YR328
1206R	22	X5	DF		3-10	26-11-21	TB2201Y	B009	1A		D40646J	B08			YC053-YD158, YL951-YR328
1206Z			DF		0-0	26-11-21	TB2201Y	DED			D40646J	DED			YC053-YD158, YL951-YR328
1207R	22	X5	DG		2-9	26-11-31	D40430J		23		TB2201Y	B019	1A		YC053-YD158, YL951-YR328
1207Z			DG		0-0	26-11-31	D40430J	DED			TB2201Y	DED			YC053-YD158, YL951-YR328
1208R	22	X5	DH		1-4	26-11-31	TB2201Y	B019	1A		TB2201Y	A015	1A		YC053-YD158, YL951-YR328
1208Z			DH		0-0	26-11-31	TB2201Y	DED			TB2201Y	DED			YC053-YD158, YL951-YR328
1209R	22	X5	DI		3-10	26-11-31	TB2201Y	B019	1A		D40646J	B09			YC053-YD158, YL951-YR328
1209Z			DI		0-0	26-11-31	TB2201Y	DED			D40646J	DED			YC053-YD158, YL951-YR328
2001B	22	X2	GA		1-9	24-21-31	D11114C		25		D40912J	B09			YC051-YD158, YL951-YR328
2001R	22	X2	GA		0-0	24-21-31	D11114C		13		D40912J	A09			YC051-YD158, YL951-YR328

WIRE LIST
D280A108

91-21-11
Section W0220
Page 19
Nov 12/2012

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0220	286A0220			E2-2 SHELF (continued)											
2001Z				GA	0-0	24-21-31	D11114C	DED			D40912J	DED			YC051-YD158, YL951-YR328
2002B	16	VG	GB		1-11	24-21-31	D11114B	10			D40912J	G			YC051
2002B	16	VG	GB		1-10	24-21-31	D11114B	10			D40912J	G			YC052-YC065
2002B	16	HQ	GB		1-10	24-21-31	D11114B	10			D40912J	G			YC067-YD158, YL951-YR328
2002R	16	VG	GB		0-0	24-21-31	D11114B	8			D40912J	F			YC051-YC065
2002R	16	HQ	GB		0-0	24-21-31	D11114B	8			D40912J	F			YC067-YD158, YL951-YR328
2002Z				GB	0-0	24-21-31	GD02207	ST..	1A		D40912J	A10			YC051-YD158, YL951-YR328
2003B	22	PB	GC		2-3	24-22-11	D40456J	J			D40360J	11			YC051-YD158, YL951-YR328
2003R	22	PB	GC		0-0	24-22-11	D40456J	K			D40360J	10			YC051-YD158, YL951-YR328
2004B	22	PB	GD		2-5	24-22-31	D43050J	A07			D40360J	13			YC051-YD158, YL951-YR328
2004R	22	PB	GD		0-0	24-22-31	D43050J	B07			D40360J	12			YC051-YD158, YL951-YR328
2005B	22	PB	GE		2-2	24-23-11	D40520J	B14			D40360J	9			YC051-YD158, YL951-YR328
2005R	22	PB	GE		0-0	24-23-11	D40520J	A14			D40360J	8			YC051-YD158, YL951-YR328
2008B	24	Y2	GH		3-3	21-31-22	D40520J	B08			D10738B	A08			YC051-YD158, YL951-YR328
2008R	24	Y2	GH		0-0	21-31-22	D40520J	A08			D10738B	A07			YC051-YD158, YL951-YR328
2008Z				GH	0-0	21-31-22	D40520J	PERG	1F		D10738B	PERG	1A		YC051-YD158, YL951-YR328
2009B	24	Y2	GI		3-4	21-31-22	D40520J	B07			D10738A	A02			YC051-YD158, YL951-YR328
2009R	24	Y2	GI		0-0	21-31-22	D40520J	A07			D10738A	A01			YC051-YD158, YL951-YR328
2009Z				GI	0-0	21-31-22	D40520J	PERG	1F		D10738A	PERG	1A		YC051-YD158, YL951-YR328
2010B	24	Y2	GJ		2-5	21-31-22	D10738A	A08			D40240J	A04			YC051-YD158, YL951-YR328
2010R	24	Y2	GJ		0-0	21-31-22	D10738A	A07			D40240J	A03			YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0220

Page 20

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Fam	Description FT-IN Diagram		From Equip Term Type Splice				To Equip Term Type Splice Effectivity				
W0220	286A0220				E2-2 SHELF (continued)										
2010Z				GJ	0-0	21-31-22	D10738A	PERG	1A		D40240J	PERG	1F	YC051-YD158, YL951-YR328	
2011B	24	Y2		GK	2-5	21-31-22	D10738A		A10		D40240J		A06	YC051-YD158, YL951-YR328	
2011R	24	Y2		GK	0-0	21-31-22	D10738A		A09		D40240J		A05	YC051-YD158, YL951-YR328	
2011Z				GK	0-0	21-31-22	D10738A	PERG	1A		D40240J	PERG	1F	YC051-YD158, YL951-YR328	
2012B	24	Y2		GL	1-10	21-31-24	D10738B		A14		D40380J		A02	YC051-YD158, YL951-YR328	
2012R	24	Y2		GL	0-0	21-31-24	D10738B		A13		D40380J		A03	YC051-YD158, YL951-YR328	
2012Z				GL	0-0	21-31-24	D10738B	PERG	1A		D40380J	PERG	1F	YC051-YD158, YL951-YR328	
2013B	24	Y2		GM	1-10	21-31-24	D10738B		A10		D40380J		A08	YC051-YD158, YL951-YR328	
2013R	24	Y2		GM	0-0	21-31-24	D10738B		A09		D40380J		A09	YC051-YD158, YL951-YR328	
2013Z				GM	0-0	21-31-24	D10738B	PERG	1A		D40380J	PERG	1F	YC051-YD158, YL951-YR328	
2014B	24	Y2		GN	1-10	21-31-24	D10738B		A06		D40380J		A06	YC051-YD158, YL951-YR328	
2014R	24	Y2		GN	0-0	21-31-24	D10738B		A05		D40380J		A07	YC051-YD158, YL951-YR328	
2014Z				GN	0-0	21-31-24	D10738B	PERG	1A		D40380J	PERG	1F	YC051-YD158, YL951-YR328	
2015B	24	Y2		GP	1-10	21-31-24	D10738B		A04		D40380J		A04	YC051-YD158, YL951-YR328	
2015R	24	Y2		GP	0-0	21-31-24	D10738B		A03		D40380J		A05	YC051-YD158, YL951-YR328	
2015Z				GP	0-0	21-31-24	D10738B	PERG	1A		D40380J	PERG	1F	YC051-YD158, YL951-YR328	
2016B	22	PB		GQ	2-11	49-41-11	D11478A		11		D11114C		46	YC051-YD158, YL951-YR328	
2016R	22	PB		GQ	0-0	49-41-11	D11478A		10		D11114C		59	YC051-YD158, YL951-YR328	
2017B	20	X2		BM	2-9	31-35-05	D40348J		B06		D40130J		B15	YL963-YL999, YN236-YR328	

WIRE LIST
D280A108

91-21-11
Section W0220
Page 21
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W0220	286A0220			E2-2 SHELF (continued)											
2017R	20	X2	BM		0-0	31-35-05	D40348J	A06			D40130J	A15			YL963-YL999, YN236-YR328
2017Z			BM		0-0	31-35-05	D40348J	PERG	1F		D40130J	PERG	1F		YL963-YL999, YN236-YR328
2018B	22	PB	GS		2-11	49-41-11	D11478A	17			D11114C	57			YC051-YC064
2018B	22	PB	GS		2-11	49-41-11	D11478A	17			D11114C	44			YC065-YD158, YL951-YR328
2018R	22	PB	GS		0-0	49-41-11	D11478A	16			D11114C	44			YC051-YC064
2018R	22	PB	GS		0-0	49-41-11	D11478A	16			D11114C	57			YC065-YD158, YL951-YR328
2019B	22	PB	GT		2-11	49-41-11	D11478A	63			D11114C	11			YC051-YD158, YL951-YR328
2019R	22	PB	GT		0-0	49-41-11	D11478A	62			D11114C	2			YC051-YD158, YL951-YR328
2020B	22	PB	GU		2-11	49-41-11	D11478A	25			D11114C	43			YC051-YD158, YL951-YR328
2020R	22	PB	GU		0-0	49-41-11	D11478A	24			D11114C	30			YC051-YD158, YL951-YR328
2021B	22	PB	GV		2-11	49-41-11	D11478A	44			D11114C	58			YC051-YD158, YL951-YR328
2021R	22	PB	GV		0-0	49-41-11	D11478A	43			D11114C	45			YC051-YD158, YL951-YR328
2022B	22	PB	GW		2-11	49-41-11	D11478A	31			D11114C	36			YC051-YD158, YL951-YR328
2022R	22	PB	GW		0-0	49-41-11	D11478A	30			D11114C	23			YC051-YD158, YL951-YR328
2023B	22	PB	GX		2-11	49-41-11	D11478A	56			D11114C	35			YC051-YD158, YL951-YR328
2023R	22	PB	GX		0-0	49-41-11	D11478A	55			D11114C	22			YC051-YD158, YL951-YR328
2024B	16	VG	GY		3-0	49-41-11	D11478B	3			D11114B	18			YC051
2024B	16	VG	GY		2-11	49-41-11	D11478B	3			D11114B	18			YC052-YD158, YL951-YR328
2024R	16	VG	GY		0-0	49-41-11	D11478B	1			D11114B	25			YC051-YD158, YL951-YR328
2024Z			GY		0-0	49-41-11	D11478B			AK	D11114B			AL	YC051-YD158, YL951-YR328
2025B	16	VG	GZ		3-0	49-41-11	D11478B	4			D11114B	24			YC051

WIRE LIST

D280A108

91-21-11

Section W0220

Page 22

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0220	286A0220				E2-2 SHELF (continued)										
2025B	16	VG	GZ		2-11	49-41-11	D11478B	4			D11114B	24			YC052-YD158, YL951-YR328
2025R	16	VG	GZ		0-0	49-41-11	D11478B	2			D11114B	26			YC051-YD158, YL951-YR328
2025Z			GZ		0-0	49-41-11	D11478B			AK	D11114B			AL	YC051-YD158, YL951-YR328
2026B	22	X2	HA		2-11	49-41-11	D11114C	66			D40928J	A06			YC051-YD158, YL951-YR328
2026R	22	X2	HA		0-0	49-41-11	D11114C	67			D40928J	B05			YC051-YD158, YL951-YR328
2026Z			HA		0-0	49-41-11	D11114C	65			D40928J	B06			YC051-YD158, YL951-YR328
2027B	22	X2	HB		2-11	49-41-11	D11114C	53			D40928J	B07			YC051-YD158, YL951-YR328
2027R	22	X2	HB		0-0	49-41-11	D11114C	54			D40928J	A07			YC051-YD158, YL951-YR328
2027Z			HB		0-0	49-41-11	D11114C	52			D40928J	A08			YC051-YD158, YL951-YR328
2028B	22	X2	HC		2-11	49-41-11	D11114C	41			D40928J	A09			YC051-YD158, YL951-YR328
2028R	22	X2	HC		0-0	49-41-11	D11114C	42			D40928J	B08			YC051-YD158, YL951-YR328
2028Z			HC		0-0	49-41-11	D11114C	40			D40928J	B09			YC051-YD158, YL951-YR328
2029B	24	PL	HD		2-11	49-41-11	D11114C	38			D40928J	B01			YC051-YD158, YL951-YR328
2029R	24	PL	HD		0-0	49-41-11	D11114C	39			D40928J	A01			YC051-YD158, YL951-YR328
2030B	24	Y2	HE		2-2	73-21-11	D40430J	7			D40130J	A06			YC051-YD158, YL951-YR328
2030R	24	Y2	HE		0-0	73-21-11	D40430J	8			D40130J	B06			YC051-YD158, YL951-YR328
2030Z			HE		0-0	73-21-11	D40430J	31			D40130J	PERG	1F		YC051-YD158, YL951-YR328
2031B	24	Y2	HF		3-6	73-24-11	D40724J	A09			TB2201Y	A017	1A		YC051-YD158, YL951-YR328
2031R	24	Y2	HF		0-0	73-24-11	D40724J	B09			TB2201Y	B015	1A		YC051-YD158, YL951-YR328

WIRE LIST
D280A108

91-21-11
Section W0220
Page 23
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W0220	286A0220				E2-2 SHELF (continued)											
2031Z				HF	0-0	73-24-11	D40724J	PERG	1F		GB02201	ST..	1A		YC051-YD158, YL951-YR328	
2032B	24	Y2	HG		3-6	73-24-11	D40126J	A14			TB2201Y	A017	1A		YC051-YD158, YL951-YR328	
2032R	24	Y2	HG		0-0	73-24-11	D40126J	B14			TB2201Y	B015	1A		YC051-YD158, YL951-YR328	
2032Z			HG		0-0	73-24-11	D40126J	PERG	1F		GB02201	ST..	1A		YC051-YD158, YL951-YR328	
2033B	24	Y2	HH		3-6	73-24-11	D40724J	A14			TB2201Y	A017	1A		YC051-YD158, YL951-YR328	
2033R	24	Y2	HH		0-0	73-24-11	D40724J	B14			TB2201Y	B015	1A		YC051-YD158, YL951-YR328	
2033Z			HH		0-0	73-24-11	D40724J	PERG	1F		GB02201	ST..	1A		YC051-YD158, YL951-YR328	
2035B	24	Y2	HJ		1-6	73-24-12	D40450J	A02			D40130J	A11			YC051-YD158, YL951-YR328	
2035R	24	Y2	HJ		0-0	73-24-12	D40450J	B02			D40130J	B11			YC051-YD158, YL951-YR328	
2035Z			HJ		0-0	73-24-12	D40450J	PERG	1F		D40130J	PERG	1F		YC051-YD158, YL951-YR328	
2037B	24	Y2	HL		2-11	77-12-21	D40450J	A11			D40136J	A08			YC051-YD158, YL951-YR328	
2037R	24	Y2	HL		0-0	77-12-21	D40450J	B11			D40136J	B08			YC051-YD158, YL951-YR328	
2037Z			HL		0-0	77-12-21	D40450J	PERG	1F		D40136J	PERG	1F		YC051-YD158, YL951-YR328	
2038B	22	VX	HM		1-6	77-31-11	D40450J	A08			D40130J	A02			YC051-YD158, YL951-YR328	
2038W	22	VX	HM		0-0	77-31-11	D40450J	B08			D40130J	B02			YC051-YD158, YL951-YR328	
2038Z			HM		0-0	77-31-11	D40450J	A09			D40130J	B01			YC051-YD158, YL951-YR328	
2039B	22	VX	HN		1-7	77-31-11	D40724J	A04			D40126J	A04			YC051-YD158, YL951-YR328	
2039W	22	VX	HN		0-0	77-31-11	D40724J	B04			D40126J	B04			YC051-YD158, YL951-YR328	
2039Z			HN		0-0	77-31-11	D40724J	A05			D40126J	A05			YC051-YD158, YL951-YR328	

WIRE LIST

D280A108

91-21-11

Section W0220

Page 24

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0220	286A0220			E2-2 SHELF (continued)											
2040B	22	X2	HP		1-6	78-36-11	D40450J	A03			D40130J	A10			YC051-YD158, YL951-YR328
2040R	22	X2	HP		0-0	78-36-11	D40450J	B03			D40130J	B10			YC051-YD158, YL951-YR328
2040Z			HP		0-0	78-36-11	D40450J	DED			D40130J	DED			YC051-YD158, YL951-YR328
2041B	22	PB	HQ		1-7	78-36-11	D40724J	A12			D40126J	A12			YC051-YD158, YL951-YR328
2041R	22	PB	HQ		0-0	78-36-11	D40724J	B12			D40126J	B12			YC051-YD158, YL951-YR328
2042B	22	X2	HR		1-6	78-36-11	D40450J	A04			D40130J	A12			YC051-YD158, YL951-YR328
2042R	22	X2	HR		0-0	78-36-11	D40450J	B04			D40130J	B12			YC051-YD158, YL951-YR328
2042Z			HR		0-0	78-36-11	D40450J	DED			D40130J	DED			YC051-YD158, YL951-YR328
2043B	22	PB	HS		1-7	78-36-11	D40724J	A13			D40126J	A13			YC051-YD158, YL951-YR328
2043R	22	PB	HS		0-0	78-36-11	D40724J	B13			D40126J	B13			YC051-YD158, YL951-YR328
2044B	24	Y2	HT		2-0	73-24-11	D40348J	A08			TB2201Y	A019	1A		YC051-YD158, YL951-YR328
2044R	24	Y2	HT		0-0	73-24-11	D40348J	B08			TB2201Y	B017	1A		YC051-YD158, YL951-YR328
2044Z			HT		0-0	73-24-11	D40348J	PERG	1F		GB02201	ST..	1A		YC051-YD158, YL951-YR328
2045B	24	Y2	HU		3-2	73-24-11	D40450J	A07			TB2201Y	A019	1A		YC051-YD158, YL951-YR328
2045R	24	Y2	HU		0-0	73-24-11	D40450J	B07			TB2201Y	B017	1A		YC051-YD158, YL951-YR328
2045Z			HU		0-0	73-24-11	D40450J	PERG	1F		GB02201	ST..	1A		YC051-YD158, YL951-YR328
2046B	24	Y2	HV		3-1	73-24-11	D40130J	A05			TB2201Y	A019	1A		YC051-YD158, YL951-YR328
2046R	24	Y2	HV		0-0	73-24-11	D40130J	B05			TB2201Y	B017	1A		YC051-YD158, YL951-YR328
2046Z			HV		0-0	73-24-11	D40130J	PERG	1F		GB02201	ST..	1A		YC051-YD158, YL951-YR328

WIRE LIST
D280A108

91-21-11
Section W0220
Page 25
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0220	286A0220			E2-2 SHELF (continued)											
2047B	22	X2		HW	2-11	49-41-11	D11478A	27			D11114C	9			YC051-YD158, YL951-YR328
2047R	22	X2		HW	0-0	49-41-11	D11478A	14			D11114C	1			YC051-YD158, YL951-YR328
2047Z				HW	0-0	49-41-11	D11478A	DED			D11114C	10			YC051-YD158, YL951-YR328
2201B	24	Y2		KA	3-5	31-35-04	D40348J	B11			D10738A	A06			YL963-YL999, YN236-YR328
2201R	24	Y2		KA	0-0	31-35-04	D40348J	A11			D10738A	A05			YL963-YL999, YN236-YR328
2201Z				KA	0-0	31-35-04	D40348J	PERG	1F		D10738A	PERG	1A		YL963-YL999, YN236-YR328
3001B	16	VH		WA	1-11	24-21-31	D11114B	13			D40912J	J			YC051
3001B	16	VH		WA	1-10	24-21-31	D11114B	13			D40912J	J			YC052-YD158, YL951-YR328
3001R	16	VH		WA	0-0	24-21-31	D11114B	5			D40912J	H			YC051-YD158, YL951-YR328
3001Y	16	VH		WA	0-0	24-21-31	D11114B	6			D40912J	K			YC051-YD158, YL951-YR328
3001Z				WA	0-0	24-21-31	GD02207	ST..	1A		D40912J	B10			YC051-YD158, YL951-YR328
3002B	22	PC		WB	2-11	49-41-11	D11478A	34			D11114C	34			YC051-YD158, YL951-YR328
3002R	22	PC		WB	0-0	49-41-11	D11478A	33			D11114C	8			YC051-YD158, YL951-YR328
3002Y	22	PC		WB	0-0	49-41-11	D11478A	35			D11114C	18			YC051-YD158, YL951-YR328
3201B	22	PC		YA	2-11	49-41-11	D11478A	9			D11114C	33			YC051-YD158, YL951-YR328
3201R	22	PC		YA	0-0	49-41-11	D11478A	8			D11114C	21			YC051-YD158, YL951-YR328
3201Y	22	PC		YA	0-0	49-41-11	D11478A	1			D11114C	20			YC051-YD158, YL951-YR328
4001B	20	U4		A6	2-11	24-21-31	D11114C	27			D40942J	B03			YC051-YD158, YL951-YR328
4001G	20	U4		A6	0-0	24-21-31	D11114C	15			D40942J	B04			YC051-YD158, YL951-YR328
4001R	20	U4		A6	0-0	24-21-31	D11114C	6			D40942J	A03			YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0220

Page 26

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0220	286A0220			E2-2 SHELF (continued)											
4001Y	20	U4		A6	0-0	24-21-31	D11114C	14			D40942J	A04			YC051-YD158, YL951-YR328
4001Z				A6	0-0	24-21-31	D11114C	DED			D40942J	DED			YC051-YD158, YL951-YR328
FRAK					0-0	49-41-11	D11478B			AK	D11478B	8			YC051-YD158, YL951-YR328
FRAL					0-0	49-41-11	D11114B			AL	D11114B	23			YC051-YD158, YL951-YR328

WIRE LIST
D280A108

91-21-11
Section W0220
Page 27 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY	Fam FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W0311	286A0311	E3-1 ELECTRONIC SHELF - LEFT			
0002	16 CQ	2-5 31-62-11	D03973C 2	D41837J 4	ALL
0003	14 CQ	2-4 31-62-11	D03973C 7	GD03973 DC.. E	ALL
0005	14 CQ	2-4 31-62-11	D03973C 8	GD03973 DC.. E	ALL
0006	22 PA	3-6 30-31-12	D03973B F12	SP00889 W	YL968-YL999, YN236-YR328
0007	22 PA	3-3 30-31-12	D03973E F12	SP00891 W	YL968-YL999, YN236-YR328
0008	22 PA	3-5 30-31-12	D40448J B04	SP00889 W	YL968-YL999, YN236-YR328
0009	22 PA	3-5 30-31-12	D40448J A04	SP00891 W	YL968-YL999, YN236-YR328
0010	16 PA	1-11 31-62-11	D03973C 9	GD03103 ST.. 1	ALL
0011	16 PA	1-11 31-62-11	D03973C 3	GD03103 ST.. 1	ALL
0012	24 PK	2-8 31-62-14	D49994J B03	TB3102Y B001 1A	YC051-YD157
0012	24 PK	2-9 31-62-14	D49994J B03	TB3102Y B001 1A	YD158-YR328
0013	24 PK	2-8 31-62-14	TB3102Y B001 1A	D03973A A11	ALL
0014	24 PK	3-8 31-62-14	TB3102Y B001 1A	D03975A A11	ALL
0015	24 PK	2-7 31-62-14	D03973B H09	TB3102Y B005 1A	ALL
0016	24 PK	3-7 31-62-14	D03975B H09	TB3102Y B005 1A	ALL
0017	24 PK	3-0 31-62-14	TB3102Y B005 1A	D40460J A09	ALL
0018	24 PK	2-0 31-62-15	D03973A H08	D43155J A01	ALL
0019	24 PK	2-0 31-62-15	D03973A E08	D43155J A02	ALL
0020	24 PK	2-0 31-62-15	D03973A B08	D43155J A03	ALL
0021	24 PK	1-10 31-62-15	SM00002 W	D03973D B07	ALL
0022	24 PK	1-9 31-62-25	SM00002 W	D03975D B07	ALL
0023	24 PK	1-6 31-62-15	D43155J A04	SM00002 W	YC051-YC052
0023	24 PK	1-7 31-62-15	D43155J A04	SM00002 W	YC053-YR328
0025	22 PA	1-9 31-62-41	D03973E F07	GD03103 DC.. 1	ALL
0026	22 PA	1-10 31-62-41	D03973D C10	GD03103 DC.. 1	ALL
0027	24 G6	3-0 74-31-11	D40516J A05	TB3102Y B003 1A	ALL
0028	24 G6	2-8 74-31-11	D03973B F09	TB3102Y B003 1A	ALL
0029	24 G6	3-8 74-31-11	D03975B F09	TB3102Y B003 1A	ALL
0030	24 G6	3-0 74-31-11	D40516J B04	TB3102Y A003 1A	ALL
0031	24 G6	2-8 74-31-11	D03973B C14	TB3102Y A003 1A	ALL
0032	24 G6	3-8 74-31-11	D03975B C14	TB3102Y A003 1A	ALL
0033	24 PK	2-11 74-31-11	D40516J A07	TB3102Y A005 1A	ALL
0034	24 PK	2-8 74-31-11	D03973A A07	TB3102Y A005 1A	ALL
0035	24 G6	3-7 74-31-11	D03975A A07	TB3102Y A005 1A	ALL
0036	24 G6	3-0 76-21-11	D40460J A06	TB3102Y A009 1A	ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0311	286A0311				E3-1 ELECTRONIC SHELF - LEFT (continued)											
0037	24		G6		2-6	76-21-11		TB3102Y	A009	1A		D03973B	H02			ALL
0038	24		G6		2-10	76-21-11		TB3102Y	A009	1A		D03973D	H02			ALL
0039	24		G6		3-6	76-21-11		TB3102Y	B009	1A		D03975B	H02			ALL
0040	24		G6		3-7	76-21-11		TB3102Y	B009	1A		D03975D	H02			ALL
0041	24		G6		0-7	76-21-11		TB3102Y	A009	1A		TB3102Y	B009	1A		ALL
0042	24		PK		2-5	73-21-31		D43145J	A06			TB3102Y	A011	1A		ALL
0043	24		PK		2-5	73-21-31		D43145J	A07			TB3102Y	B011	1A		ALL
0044	24		PK		2-5	73-21-31		D43145J	A08			TB3102Y	A013	1A		ALL
0045	24		PK		2-5	73-21-31		D43145J	A09			TB3102Y	B013	1A		ALL
0046	24		PK		2-5	73-21-31		D43145J	A10			TB3102Y	A015	1A		ALL
0047	24		PK		3-6	73-21-31		TB3102Y	A011	1A		D03975B	B08			ALL
0048	24		G6		3-6	73-21-31		TB3102Y	B011	1A		D03975B	E07			ALL
0049	24		PK		3-6	73-21-31		TB3102Y	A013	1A		D03975B	J08			ALL
0050	24		G6		3-6	73-21-31		TB3102Y	B013	1A		D03975B	C06			ALL
0051	24		G6		3-6	73-21-31		TB3102Y	A015	1A		D03975B	A02			ALL
0052	24		PK		2-6	73-21-31		TB3102Y	A015	1A		D03973B	A02			ALL
0053	24		PK		2-6	73-21-31		TB3102Y	B013	1A		D03973B	C06			ALL
0054	24		PK		2-6	73-21-31		TB3102Y	A013	1A		D03973B	J08			ALL
0055	24		PK		2-6	73-21-31		TB3102Y	B011	1A		D03973B	E07			ALL
0056	24		PK		2-6	73-21-31		TB3102Y	A011	1A		D03973B	B08			ALL
0057	24		G6		2-10	73-21-12		D40516J	B05			TB3102Y	B015	1A		ALL
0058	24		G6		3-6	73-21-12		TB3102Y	B015	1A		D03975B	J07			ALL
0059	24		G6		2-6	73-21-12		TB3102Y	B015	1A		D03973B	J07			ALL
0060	24		G6		2-11	73-22-11		D40460J	A07			TB3102Y	A017	1A		ALL
0061	24		G6		3-6	73-22-11		TB3102Y	A017	1A		D03975B	D13			ALL
0062	24		G6		2-6	73-22-11		TB3102Y	A017	1A		D03973B	D13			ALL
0063	24		G6		2-11	73-22-31		D40460J	A03			TB3102Y	B017	1A		ALL
0064	24		G6		3-6	73-22-31		TB3102Y	B017	1A		D03975A	F12			ALL
0065	24		G6		2-6	73-22-31		TB3102Y	B017	1A		D03973A	F12			ALL
0066	24		PK		2-10	73-23-11		D40516J	A06			TB3102Y	A019	1A		ALL
0067	24		PK		2-11	73-23-11		D40460J	A04			TB3102Y	B019	1A		ALL
0068	24		PK		2-10	73-23-11		D40460J	A05			TB3102Y	A021	1A		ALL
0069	24		G6		3-6	73-23-11		TB3102Y	A019	1A		D03975B	A11			ALL
0070	24		PK		3-6	73-23-11		TB3102Y	B019	1A		D03975B	D08			ALL
0071	24		PK		3-5	73-23-11		TB3102Y	A021	1A		D03975A	D08			ALL
0072	24		PK		2-6	73-23-11		TB3102Y	B019	1A		D03973B	D08			ALL
0073	24		PK		2-6	73-23-11		TB3102Y	A019	1A		D03973B	A11			ALL
0074	24		PK		2-5	73-23-11		TB3102Y	A021	1A		D03973A	D08			ALL
0075	24		G6		2-9	73-31-11		D40516J	B06			TB3102Y	B021	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W0311	286A0311	E3-1 ELECTRONIC SHELF - LEFT (continued)													
0076	24	G6	2-4	73-31-11	TB3102Y	B021	1A		D03973B	B14			ALL		
0077	24	G6	3-5	73-31-11	TB3102Y	B021	1A		D03975B	B14			ALL		
0078	24	G6	2-9	73-32-11	D40516J	A04			TB3102Y	A023	1A		ALL		
0079	24	G6	2-4	73-32-11	TB3102Y	A023	1A		D03973B	F02			ALL		
0080	24	G6	3-5	73-32-11	TB3102Y	A023	1A		D03975B	F02			ALL		
0081	24	B6	1-11	80-11-11	D40448J	A01			TB3102Y	B023	1A		ALL		
0082	24	B6	1-11	80-11-11	D40448J	B01			TB3102Y	A025	1A		ALL		
0083	24	B6	2-4	80-11-11	TB3102Y	B023	1A		D03973B	H04			ALL		
0084	24	B6	2-5	80-11-11	TB3102Y	A025	1A		D03973B	K12			ALL		
0085	24	B6	3-5	80-11-11	TB3102Y	B023	1A		D03975B	H04			ALL		
0086	24	B6	3-5	80-11-11	TB3102Y	A025	1A		D03975B	K12			ALL		
0087	22	G5	2-11	49-62-11	D45205J	B01			TB3102Y	B025	1A		ALL		
0088	22	G5	3-4	49-62-11	TB3102Y	B025	1A		D03975E	H09			ALL		
0089	22	G5	2-8	49-62-11	TB3102Y	B025	1A		D03973E	H09			ALL		
0090	24	PK	2-1	29-31-11	D49994J	A04			TB3102Z	B029	1A		YC051-YD157		
0090	24	PK	2-3	29-31-11	D49994J	A04			TB3102Z	B029	1A		YD158-YR328		
0091	24	PK	2-1	29-31-11	D49994J	B04			TB3102Y	A033	1A		YC051-YD157		
0091	24	PK	2-2	29-31-11	D49994J	B04			TB3102Y	A033	1A		YD158-YR328		
0092	24	PK	2-1	29-31-11	D49994J	A05			TB3102Z	A029	1A		YC051-YD157		
0092	24	PK	2-3	29-31-11	D49994J	A05			TB3102Z	A029	1A		YD158-YR328		
0093	24	PK	2-2	29-31-11	TB3102Z	B029	1A		D03973A	B06			ALL		
0094	24	PK	2-2	29-31-11	TB3102Z	B029	1A		D03973A	K04			ALL		
0095	24	PK	2-1	29-31-11	TB3102Z	B029	1A		D03973B	F14			ALL		
0096	24	PK	3-2	29-31-11	TB3102Z	B029	1A		D03975A	B06			ALL		
0097	24	PK	3-2	29-31-11	TB3102Z	B029	1A		D03975A	K04			ALL		
0098	24	PK	3-1	29-31-11	TB3102Z	B029	1A		D03975B	F14			ALL		
0099	24	PK	2-2	29-31-11	TB3102Y	A033	1A		D03973A	J04			ALL		
0100	24	PK	3-2	29-31-11	TB3102Y	A033	1A		D03975A	J04			ALL		
0101	24	PK	2-2	29-31-11	TB3102Z	A029	1A		D03973A	A06			ALL		
0102	24	PK	2-1	29-31-11	TB3102Z	A029	1A		D03973B	E14			ALL		
0103	24	PK	3-2	29-31-11	TB3102Z	A029	1A		D03975A	A06			ALL		
0104	24	PK	3-1	29-31-11	TB3102Z	A029	1A		D03975B	E14			ALL		
0105	24	PK	2-3	29-32-11	D45131J	A02			D03973A	A09			ALL		
0106	24	PK	2-3	29-32-11	D45131J	B02			D03973A	B09			ALL		
0110	22	G5	2-5	22-11-18	D45111J	A02			D03667B	K06			ALL		
0111	22	CQ	1-5	34-51-41	D40516J	B10			SM00003		W		ALL		
0112	22	CQ	2-0	34-51-41	SM00003		W		D03973B	G10			ALL		
0113	22	CQ	1-8	34-51-41	SM00003		W		D03975B	G10			ALL		
0114	22	CQ	1-6	34-51-41	D45205J	A01			SM00004		W		ALL		

WIRE LIST

D280A108

91-21-11

Section W0310

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0311	286A0311				E3-1 ELECTRONIC SHELF - LEFT (continued)										
0115	22		CQ		2-0	34-51-41	SM00004				D03973B	C08			ALL
0116	22		CQ		1-8	34-51-41	SM00004				D03975B	C08			ALL
0117	24		PK		2-0	34-41-11	D03973A		C13		SM00005		W		YC051-YC052
0118	24		PK		2-2	34-41-11	SM00005			W	D04267J	B16			YC051-YC052
0119	22		PA		1-6	34-61-12	D43155J		A18		SM00006		W		YC051-YC052
0119	22		PA		1-7	34-61-12	D43155J		A18		SM00006		W		YC053-YR328
0120	22		PA		2-0	34-61-12	SM00006			W	D03973B	B12			ALL
0121	22		PA		1-8	34-61-12	SM00006			W	D03975B	B12			ALL
0122	22		PA		1-6	34-61-12	D43155J		A17		SM00007		W		YC051-YC052
0122	22		PA		1-7	34-61-12	D43155J		A17		SM00007		W		YC053-YR328
0123	22		PA		1-9	34-61-12	SM00007			W	D03973E	B12			ALL
0124	22		PA		1-8	34-61-12	SM00007			W	D03975E	B12			ALL
0127	22		PA		1-5	34-21-15	D40516J		B02		SM00008		W		ALL
0128	22		PA		1-9	34-21-15	SM00008			W	D03973E	G02			ALL
0129	22		PA		1-8	34-21-15	SM00008			W	D03975E	G02			ALL
0130	22		PA		1-5	34-21-15	D40516J		A02		SM00009		W		ALL
0131	22		PA		2-0	34-21-15	SM00009			W	D03973B	G02			ALL
0132	22		PA		1-8	34-21-15	SM00009			W	D03975B	G02			ALL
0133	24		PK		2-0	31-62-15	D03973B		G07		D43145J	B13			ALL
0134	20		PA		2-1	34-61-11	D41837J		6		D45205J	A08			YC053-YD157
0134	20		CQ		2-1	34-61-11	D41837J		6		D45205J	A08			YD158-YR328
0135	20		PA		2-1	34-61-11	D41837J		8		D45205J	A09			YC053-YD157
0135	20		CQ		2-1	34-61-11	D41837J		8		D45205J	A09			YD158-YR328
0136	20		GA		2-0	34-61-11	D41817J		1		D43145J	A03			YC051-YC052
0136	20		PA		2-0	SPARE	D41817J		1		D43145J	A03			YD158-YR328
0137	20		GA		2-0	34-61-11	D41817J		2		D43145J	A04			YC051-YC052
0137	20		PA		2-0	SPARE	D41817J		2		D43145J	A04			YD158-YR328
0138	20		CQ		2-1	34-21-11	D41837J		5		D45205J	A02			ALL
0139	20		CQ		2-1	34-21-11	D41837J		9		D45205J	A04			ALL
0140	20		PA		2-11	SPARE	D04271J		A03		D40460J	A08			YD158-YN260, YR301-YR328
0140	20		PA		2-11	23-11-16	D04271J		A03		D40460J	A08			YN501
0141	20		CQ		2-5	34-57-11	D41837J		3		D42005J	A01			YC051-YD157
0141	20		CQ		2-7	34-57-11	D41837J		3		D42005J	A01			YD158-YR328
0142	22		CQ		2-6	34-57-11	D42005J		A09		D03651C	2			YC051-YD157
0142	22		CQ		2-8	34-57-11	D42005J		A09		D03651C	2			YD158-YR328
0143	20		CQ		2-1	34-57-11	D03651C		4		GD03102	AC..	1A		ALL
0144	20		PA		2-1	34-57-11	D03651C		3		GD03102	ST..	1A		ALL
0145	22		PA		2-1	34-57-11	D03651B		C13		GD03102	DC..	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 4

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W0311	286A0311				E3-1 ELECTRONIC SHELF - LEFT (continued)										
0146	24		PK		1-0	34-57-11	D03651B		C05		SM00001		W		ALL
0147	24		PK		1-0	34-57-11	D03651B		C08		SM00001		W		ALL
0148	24		PK		1-0	34-57-11	D03651B		C09		SM00001		W		ALL
0149	22		PA		2-10	34-57-11	D03651B		B15		D40460J	A02			ALL
0150	22		PA		2-10	34-33-11	D41817J		8		D03667C	8			ALL
0151	20		PA		1-9	34-33-11	D03667C		3		GD03101	AC..	1A		ALL
0152	20		PA		1-9	34-33-11	D03667C		2		GD03101	ST..	1A		ALL
0153	24		PK		0-3	34-33-11	D03667B		J02		D03667B	J04			ALL
0154	24		PK		0-3	34-33-11	D03667B		E03		D03667B	F02			ALL
0155	24		PK		0-3	34-33-11	D03667B		B05		D03667B	C05			ALL
0156	22		PA		1-10	34-33-11	D03667B		F05		GD03101	DC..	1A		ALL
0157	22		PA		1-10	34-33-11	D03667B		F06		GD03101	DC..	1A		ALL
0158	24		PK		3-2	34-33-11	D40460J		A01		D03667B	F04			ALL
0160	24		PK		2-6	34-45-11	D45111J		A01		D03973E	D04			ALL
0161	22		PA		2-11	34-41-11	D04267J		B13		TB3101Y	B061	1A		YC051-YC052
0162	22		PA		2-11	34-41-11	D04267J		B14		TB3101Y	B065	1A		YC051-YC052
0165	22		PA		2-9	34-41-11	TB3101Y		A063	1A	SP00501		W		YC051-YC052
0166	22		PA		0-7	34-41-11	TB3101Y		B061	1A	TB3101Y	B063	1A		YC051-YC052
0167	22		PA		2-9	34-49-11	D45131J		A04		TB3101Y	B063	1A		YC051-YC052
0168	22		PA		2-9	34-49-11	D45131J		B04		TB3101Y	A061	1A		YC051-YC052
0169	22		PA		2-9	34-49-11	D45131J		A01		TB3101Y	B065	1A		YC051-YC052
0170	22		PA		1-4	34-41-11	TB3101Y		A061	1A	TB3101Y	A065	1A		YC051-YC052
0171	22		PA		2-0	31-62-41	D03973B		D06		GD03103	DC..	1		ALL
0178	24		PK		3-1	31-62-42	D03973F		B09		SP03104		W		YL951-YR328
0191	24		PK		2-4	31-62-14	D40460J		B04		TB3102Y	A051	1A		ALL
0192	24		PK		2-5	31-62-14	TB3102Y		A051	1A	D03973A	A08			ALL
0193	24		G6		2-11	31-62-14	TB3102Y		A051	1A	D03975A	A08			ALL
0197	24		PK		1-9	34-41-11	D03975A		C13		SM00005		W		YC051-YC052
0198	24		PK		1-9	31-62-14	D49994J		B07		SM00012		W		YC051-YD157
0198	24		PK		1-10	31-62-14	D49994J		B07		SM00012		W		YD158-YR328
0199	24		PK		2-0	31-62-14	D03973A		K12		SM00012		W		ALL
0200	24		PK		1-9	31-62-14	D03975A		K12		SM00012		W		ALL
0220	24		PK		2-9	31-62-41	TB3101Y		A061	1A	D03973A	E02			YD158-YR328
0221	24		PK		2-9	31-62-41	TB3101Y		B061	1A	SP03103		W		YD158-YR328
0627	22		G5		1-10	34-41-11	D03973D		H06		SM00523		W		YC053-YR328
0628	22		G5		1-9	34-41-11	D03975D		H06		SM00523		W		YC053-YR328
0629	22		PA		1-6	34-41-11	D40460J		B07		SM00523		W		YC053-YD157
0629	22		G5		1-6	34-41-11	D40460J		B07		SM00523		W		YD158-YR328
1001	22		X1	MA	2-4	31-62-14	D45131J		A05		TB3102Y	A001	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0311	286A0311				E3-1 ELECTRONIC SHELF - LEFT (continued)										
1001Z				MA	0-0	31-62-14	D45131J	PERG	1F		GB03102	ST..	1A		ALL
1002	22	X1		MB	2-8	31-62-14	TB3102Y	A001	1A		D03973A	H10			ALL
1002Z				MB	0-0	31-62-14	GB03102	ST..	1A		D03973A	PERG	1A		ALL
1003	22	X1		MC	3-8	31-62-14	TB3102Y	A001	1A		D03975A	H10			ALL
1003Z				MC	0-0	31-62-14	GB03102	ST..	1A		D03975A	PERG	1A		ALL
1004	24	Y1		MD	2-8	79-31-11	TB3102Z	B053	1A		D03973B	K04			ALL
1004Z				MD	0-0	79-31-11	GB03102	ST..	1A		D03973B	PERG	1A		ALL
1005	24	Y1		ME	2-7	79-31-11	TB3102Z	B053	1A		D03975B	K04			ALL
1005Z				ME	0-0	79-31-11	GB03102	ST..	1A		D03975B	PERG	1A		ALL
1006	24	Y1		MF	2-4	79-31-11	TB3102Y	B051	1A		D03973B	J04			ALL
1006Z				MF	0-0	79-31-11	GB03102	ST..	1A		D03973B	PERG	1A		ALL
1007	24	Y1		MG	2-10	79-31-11	TB3102Y	B051	1A		D03975B	J04			ALL
1007Z				MG	0-0	79-31-11	GB03102	ST..	1A		D03975B	PERG	1A		ALL
1008	22	X1		MH	2-0	34-57-11	D03651B	C12			D42163J	A09			ALL
1008Z				MH	0-0	34-57-11	D03651B	PERG	1A		D42163J	PERG	1F		ALL
101CO				ZA	0-0	31-62-12	D03973C	= 12			D40101J	= C1			ALL
101CX			0F	ZA	1-10	31-62-12	D03973C	12	DN		D40101J	= A1			ALL
2001B	24	Y2		AA	2-4	31-62-12	D04267J	A02			TB3101Y	B001	1A		ALL
2001R	24	Y2		AA	0-0	31-62-12	D04267J	A01			TB3101Y	A001	1A		ALL
2001Z				AA	0-0	31-62-12	D04267J	PERG	1F		GB03101	ST..	1A		ALL
2002B	24	Y2		AB	2-4	31-62-12	D04267J	A04			TB3101Y	B003	1A		ALL
2002R	24	Y2		AB	0-0	31-62-12	D04267J	A03			TB3101Y	A003	1A		ALL
2002Z				AB	0-0	31-62-12	D04267J	PERG	1F		GB03101	ST..	1A		ALL
2003B	24	Y2		AC	2-2	31-62-12	D45131J	B08			TB3101Y	B005	1A		ALL
2003R	24	Y2		AC	0-0	31-62-12	D45131J	A08			TB3101Y	A005	1A		ALL
2003Z				AC	0-0	31-62-12	D45131J	PERG	1F		GB03101	ST..	1A		ALL
2004B	24	Y2		AD	2-7	31-62-12	D03973B	B01			TB3101Y	B001	1A		ALL
2004R	24	Y2		AD	0-0	31-62-12	D03973B	A01			TB3101Y	A001	1A		ALL
2004Z				AD	0-0	31-62-12	D03973B	PERG	1A		GB03101	ST..	1A		ALL
2005B	24	Y2		AE	2-7	31-62-12	D03973A	B01			TB3101Y	B003	1A		ALL
2005R	24	Y2		AE	0-0	31-62-12	D03973A	A01			TB3101Y	A003	1A		ALL
2005Z				AE	0-0	31-62-12	D03973A	PERG	1A		GB03101	ST..	1A		ALL
2006B	24	Y2		AF	2-6	31-62-12	D03973B	K15			TB3101Y	B005	1A		ALL
2006R	24	Y2		AF	0-0	31-62-12	D03973B	J15			TB3101Y	A005	1A		ALL
2006Z				AF	0-0	31-62-12	D03973B	PERG	1A		GB03101	ST..	1A		ALL
2007B	24	Y2		AG	3-7	31-62-12	D03975A	B01			TB3101Y	B003	1A		ALL
2007R	24	Y2		AG	0-0	31-62-12	D03975A	A01			TB3101Y	A003	1A		ALL
2007Z				AG	0-0	31-62-12	D03975A	PERG	1A		GB03101	ST..	1A		ALL
2008B	24	Y2		AH	3-7	31-62-12	D03975B	B01			TB3101Y	B001	1A		ALL

WIRE LIST

D280A108

91-21-11
Section W0310
Page 6
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0311	286A0311			E3-1 ELECTRONIC SHELF - LEFT (continued)											
2008R	24	Y2	AH		0-0	31-62-12	D03975B	A01			TB3101Y	A001	1A		ALL
2008Z			AH		0-0	31-62-12	D03975B	PERG	1A		GB03101	ST..	1A		ALL
2009B	24	Y2	AI		3-6	31-62-12	D03975B	K15			TB3101Y	B005	1A		ALL
2009R	24	Y2	AI		0-0	31-62-12	D03975B	J15			TB3101Y	A005	1A		ALL
2009Z			AI		0-0	31-62-12	D03975B	PERG	1A		GB03101	ST..	1A		ALL
2010B	24	Y2	AJ		2-4	31-62-13	D04267J	A10			TB3101Y	B007	1A		ALL
2010R	24	Y2	AJ		0-0	31-62-13	D04267J	A09			TB3101Y	A007	1A		ALL
2010Z			AJ		0-0	31-62-13	D04267J	PERG	1F		GB03101	ST..	1A		ALL
2011B	24	Y2	AK		2-7	31-62-13	D03973A	K01			TB3101Y	B007	1A		ALL
2011R	24	Y2	AK		0-0	31-62-13	D03973A	J01			TB3101Y	A007	1A		ALL
2011Z			AK		0-0	31-62-13	D03973A	PERG	1A		GB03101	ST..	1A		ALL
2012B	24	Y2	AL		3-7	31-62-13	D03975A	K01			TB3101Y	B007	1A		ALL
2012R	24	Y2	AL		0-0	31-62-13	D03975A	J01			TB3101Y	A007	1A		ALL
2012Z			AL		0-0	31-62-13	D03975A	PERG	1A		GB03101	ST..	1A		ALL
2013B	24	Y2	AM		2-0	31-62-15	D03973E	B15			D43145J	B12			ALL
2013R	24	Y2	AM		0-0	31-62-15	D03973E	A15			D43145J	B11			ALL
2013Z			AM		0-0	31-62-15	D03973E	PERG	1A		D43145J	PERG	1F		ALL
2014B	24	Y2	AN		2-4	31-62-15	D03973B	B15			TB3101Y	B027	1A		ALL
2014R	24	Y2	AN		0-0	31-62-15	D03973B	A15			TB3101Y	A027	1A		ALL
2014Z			AN		0-0	31-62-15	D03973B	PERG	1A		GB03101	ST..	1A		ALL
2015B	24	Y2	AP		2-3	31-62-15	D43145J	B15			TB3101Y	B027	1A		ALL
2015R	24	Y2	AP		0-0	31-62-15	D43145J	B14			TB3101Y	A027	1A		ALL
2015Z			AP		0-0	31-62-15	D43145J	PERG	1F		GB03101	ST..	1A		ALL
2016B	24	Y2	AQ		2-3	31-62-15	D43145J	B17			TB3101Y	B027	1A		ALL
2016R	24	Y2	AQ		0-0	31-62-15	D43145J	B16			TB3101Y	A027	1A		ALL
2016Z			AQ		0-0	31-62-15	D43145J	PERG	1F		GB03101	ST..	1A		ALL
2017B	24	Y2	AR		2-9	31-62-15	D03973D	B15			TB3101Z	B009	1A		ALL
2017R	24	Y2	AR		0-0	31-62-15	D03973D	A15			TB3101Z	A009	1A		ALL
2017Z			AR		0-0	31-62-15	D03973D	PERG	1A		GB03101	ST..	1A		ALL
2018B	24	Y2	AS		2-1	31-62-15	D45131J	B13			TB3101Z	B009	1A		ALL
2018R	24	Y2	AS		0-0	31-62-15	D45131J	A13			TB3101Z	A009	1A		ALL
2018Z			AS		0-0	31-62-15	D45131J	PERG	1F		GB03101	ST..	1A		ALL
2019B	24	Y2	AT		2-1	31-62-15	D45131J	B12			TB3101Z	B009	1A		ALL
2019R	24	Y2	AT		0-0	31-62-15	D45131J	A12			TB3101Z	A009	1A		ALL
2019Z			AT		0-0	31-62-15	D45131J	PERG	1F		GB03101	ST..	1A		ALL
2020B	24	Y2	AU		2-1	31-62-15	D45131J	B11			TB3101Z	B009	1A		ALL
2020R	24	Y2	AU		0-0	31-62-15	D45131J	A11			TB3101Z	A009	1A		ALL
2020Z			AU		0-0	31-62-15	D45131J	PERG	1F		GB03101	ST..	1A		ALL
2021B	24	Y2	AV		2-1	31-62-15	D45131J	B10			TB3101Z	B009	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To
Wire No.	GA CO TY	Fam FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice Effectivity
W0311	286A0311	E3-1 ELECTRONIC SHELF - LEFT (continued)		
2021R	24	Y2 AV	0-0 31-62-15 D45131J A10	TB3101Z A009 1A ALL
2021Z		AV	0-0 31-62-15 D45131J PERG 1F	GB03101 ST.. 1A ALL
2022B	24	Y2 AW	2-1 31-62-15 D45131J B09	TB3101Z B009 1A ALL
2022R	24	Y2 AW	0-0 31-62-15 D45131J A09	TB3101Z A009 1A ALL
2022Z		AW	0-0 31-62-15 D45131J PERG 1F	GB03101 ST.. 1A ALL
2023B	24	Y2 AX	2-11 31-62-15 D03973D D07	D03975B K13 ALL
2023R	24	Y2 AX	0-0 31-62-15 D03973D C07	D03975B J13 ALL
2023Z		AX	0-0 31-62-15 D03973D PERG 1A	D03975B PERG 1A ALL
2024B	24	Y2 AY	3-1 31-62-15 D03973A D07	D03975E K13 ALL
2024R	24	Y2 AY	0-0 31-62-15 D03973A C07	D03975E J13 ALL
2024Z		AY	0-0 31-62-15 D03973A PERG 1A	D03975E PERG 1A ALL
2025B	24	Y2 AZ	2-1 31-62-15 D03973D K03	D43155J A12 ALL
2025R	24	Y2 AZ	0-0 31-62-15 D03973D J03	D43155J A11 ALL
2025Z		AZ	0-0 31-62-15 D03973D PERG 1A	D43155J PERG 1F ALL
2026B	24	Y2 BA	2-4 31-62-15 D03973B D07	TB3101Y B015 1A ALL
2026R	24	Y2 BA	0-0 31-62-15 D03973B C07	TB3101Y A015 1A ALL
2026Z		BA	0-0 31-62-15 D03973B PERG 1A	GB03101 ST.. 1A ALL
2027B	24	Y2 BB	2-3 31-62-15 D43155J A14	TB3101Y B015 1A ALL
2027R	24	Y2 BB	0-0 31-62-15 D43155J A13	TB3101Y A015 1A ALL
2027Z		BB	0-0 31-62-15 D43155J PERG 1F	GB03101 ST.. 1A ALL
2028B	22	X2 BC	2-0 31-62-15 D45131J B07	TB3101Y B015 1A ALL
2028R	22	X2 BC	0-0 31-62-15 D45131J A07	TB3101Y A015 1A ALL
2028Z		BC	0-0 31-62-15 D45131J PERG 1F	GB03101 ST.. 1A ALL
2029B	24	Y2 BD	2-0 31-62-15 D45131J B14	TB3101Y B015 1A YC051-YC052
2029B	24	Y2 BD	3-9 31-62-15 SP00159	TB3101Y B015 1A YC053-YR328
2029R	24	Y2 BD	0-0 31-62-15 D45131J A14	TB3101Y A015 1A YC051-YC052
2029R	24	Y2 BD	0-0 31-62-15 SP00157	TB3101Y A015 1A YC053-YR328
2029Z		BD	0-0 31-62-15 D45131J PERG 1F	GB03101 ST.. 1A YC051-YC052
2029Z		BD	0-0 31-62-15 SP00161	GB03101 ST.. 1A YC053-YR328
2030B	24	Y2 BE	2-3 31-62-15 D03973A K10	D45131J B15 YC051-YD170
2030B	24	Y2 BE	2-0 31-62-15 D03973A K10	SM00015 W YL951-YR328
2030R	24	Y2 BE	0-0 31-62-15 D03973A J10	D45131J A15 YC051-YD170
2030R	24	Y2 BE	0-0 31-62-15 D03973A J10	SM00014 W YL951-YR328
2030Z		BE	0-0 31-62-15 D03973A PERG 1A	D45131J PERG 1F YC051-YD170
2030Z		BE	0-0 31-62-15 D03973A PERG 1A	SM00013 W YL951-YR328
2031B	24	Y2 BF	2-6 31-62-15 D03973D K10	D45131J B16 YC051-YD170
2031B	24	Y2 BF	1-10 31-62-15 D03973D K10	SM00018 W YL951-YR328
2031R	24	Y2 BF	0-0 31-62-15 D03973D J10	D45131J A16 YC051-YD170
2031R	24	Y2 BF	0-0 31-62-15 D03973D J10	SM00017 W YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0310

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0311		286A0311			E3-1 ELECTRONIC SHELF - LEFT (continued)											
2031Z					BF	0-0	31-62-15	D03973D	PERG	1A		D45131J	PERG	1F		YC051-YD170
2031Z					BF	0-0	31-62-15	D03973D	PERG	1A		SM00016		W		YL951-YR328
2032B	24		Y2		BG	2-5	31-62-15	D03973D		K15		D45151J		B06		YC051-YD157
2032R	24		Y2		BG	0-0	31-62-15	D03973D		J15		D45151J		A06		YC051-YD157
2032Z					BG	0-0	31-62-15	D03973D	PERG	1A		D45151J	PERG	1F		YC051-YD157
2033B	24		Y2		BH	2-5	31-62-15	D03973E		D07		D45151J		B07		YC051-YN260
2033R	24		Y2		BH	0-0	31-62-15	D03973E		C07		D45151J		A07		YC051-YN260
2033Z					BH	0-0	31-62-15	D03973E	PERG	1A		D45151J	PERG	1F		YC051-YN260
2034B	24		Y2		BI	2-1	77-31-11	D40448J		A03		TB3102Y		B007	1A	ALL
2034R	24		Y2		BI	0-0	77-31-11	D40448J		B03		TB3102Y		A007	1A	ALL
2034Z					BI	0-0	77-31-11	D40448J	PERG	1F		GB03102		ST..	1A	ALL
2035B	24		Y2		BJ	2-7	77-31-11	D03973B		D12		TB3102Y		B007	1A	ALL
2035R	24		Y2		BJ	0-0	77-31-11	D03973B		C12		TB3102Y		A007	1A	ALL
2035Z					BJ	0-0	77-31-11	D03973B	PERG	1A		GB03102		ST..	1A	ALL
2036B	24		Y2		BK	3-7	77-31-11	D03975B		D12		TB3102Y		B007	1A	ALL
2036R	24		Y2		BK	0-0	77-31-11	D03975B		C12		TB3102Y		A007	1A	ALL
2036Z					BK	0-0	77-31-11	D03975B	PERG	1A		GB03102		ST..	1A	ALL
2037B	22		X2		BL	2-2	49-62-11	D45205J		B08		TB3102Z		B057	1A	ALL
2037R	22		X2		BL	0-0	49-62-11	D45205J		B07		TB3102Z		A057	1A	ALL
2037Z					BL	0-0	49-62-11	D45205J	PERG	1F		GB03102		ST..	1A	ALL
2038B	22		X2		BM	2-7	49-62-11	TB3102Z		B057	1A	D03975A		D05		ALL
2038R	22		X2		BM	0-0	49-62-11	TB3102Z		A057	1A	D03975A		C05		ALL
2038Z					BM	0-0	49-62-11	GB03102		ST..	1A	D03975A	PERG	1A		ALL
2039B	22		X2		BN	2-8	49-62-11	TB3102Z		B057	1A	D03973A		D05		ALL
2039R	22		X2		BN	0-0	49-62-11	TB3102Z		A057	1A	D03973A		C05		ALL
2039Z					BN	0-0	49-62-11	GB03102		ST..	1A	D03973A	PERG	1A		ALL
2040B	22		X2		BP	2-2	49-62-11	D45205J		A06		TB3102Z		B057	1A	YC051
2040B	22		X2		BP	2-2	49-62-11	TB3102Z		B057	1A	D45205J		A06		YC052-YR328
2040R	22		X2		BP	0-0	49-62-11	D45205J		B05		TB3102Z		A057	1A	YC051
2040R	22		X2		BP	0-0	49-62-11	TB3102Z		A057	1A	D45205J		B05		YC052-YR328
2040Z					BP	0-0	49-62-11	D45205J	PERG	1F		GB03102		ST..	1A	YC051
2040Z					BP	0-0	49-62-11	GB03102		ST..	1A	D45205J	PERG	1F		YC052-YR328
2041B	24		Y2		BQ	2-6	73-24-11	D40460J		B05		TB3102Y		B035	1A	ALL
2041R	24		Y2		BQ	0-0	73-24-11	D40460J		B06		TB3102Y		A035	1A	ALL
2041Z					BQ	0-0	73-24-11	D40460J	PERG	1F		GB03102		ST..	1A	ALL
2042B	24		Y2		BR	2-2	73-24-11	D40448J		A05		TB3102Y		B037	1A	ALL
2042R	24		Y2		BR	0-0	73-24-11	D40448J		B05		TB3102Y		A037	1A	ALL
2042Z					BR	0-0	73-24-11	D40448J	PERG	1F		GB03102		ST..	1A	ALL
2043B	24		Y2		BS	2-2	73-24-11	TB3102Y		B035	1A	D03973A		B05		ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0311	286A0311				E3-1 ELECTRONIC SHELF - LEFT (continued)											
2043R	24	Y2	BS		0-0	73-24-11		TB3102Y	A035	1A		D03973A	A05			ALL
2043Z			BS		0-0	73-24-11		GB03102	ST..	1A		D03973A	PERG	1A		ALL
2044B	24	Y2	BT		2-2	73-24-11		TB3102Y	B037	1A		D03973B	B05			ALL
2044R	24	Y2	BT		0-0	73-24-11		TB3102Y	A037	1A		D03973B	A05			ALL
2044Z			BT		0-0	73-24-11		GB03102	ST..	1A		D03973B	PERG	1A		ALL
2045B	24	Y2	BU		3-2	73-24-11		TB3102Y	B035	1A		D03975A	B05			ALL
2045R	24	Y2	BU		0-0	73-24-11		TB3102Y	A035	1A		D03975A	A05			ALL
2045Z			BU		0-0	73-24-11		GB03102	ST..	1A		D03975A	PERG	1A		ALL
2046B	24	Y2	BV		3-0	73-24-11		TB3102Y	B037	1A		D03975B	B05			ALL
2046R	24	Y2	BV		0-0	73-24-11		TB3102Y	A037	1A		D03975B	A05			ALL
2046Z			BV		0-0	73-24-11		GB03102	ST..	1A		D03975B	PERG	1A		ALL
2049B	24	Y2	BY		2-3	73-24-12		D03973A	K03			TB3102Y	B039	1A		ALL
2049R	24	Y2	BY		0-0	73-24-12		D03973A	J03			TB3102Y	A039	1A		ALL
2049Z			BY		0-0	73-24-12		D03973A	PERG	1A		GB03102	ST..	1A		ALL
2050B	24	Y2	BZ		2-0	73-24-12		TB3102Y	B039	1A		D49994J	A06			YC051-YD157
2050B	24	Y2	BZ		2-1	73-24-12		TB3102Y	B039	1A		D49994J	A06			YD158-YR328
2050R	24	Y2	BZ		0-0	73-24-12		TB3102Y	A039	1A		D49994J	B05			ALL
2050Z			BZ		0-0	73-24-12		GB03102	ST..	1A		D49994J	PERG	1F		ALL
2051B	24	Y2	CA		2-10	73-24-12		TB3102Y	B073	1A		D40448J	A02			ALL
2051R	24	Y2	CA		0-0	73-24-12		TB3102Y	A073	1A		D40448J	B02			ALL
2051Z			CA		0-0	73-24-12		GB03102	ST..	1A		D40448J	PERG	1F		ALL
2052B	24	Y2	CB		2-5	73-24-12		TB3102Y	B039	1A		D40460J	B03			ALL
2052R	24	Y2	CB		0-0	73-24-12		TB3102Y	A039	1A		D40460J	B02			ALL
2052Z			CB		0-0	73-24-12		GB03102	ST..	1A		D40460J	PERG	1F		ALL
2053B	22	X2	CC		2-5	28-41-11		D04267J	B04			TB3102Y	B041	1A		ALL
2053R	22	X2	CC		0-0	28-41-11		D04267J	B03			TB3102Y	A041	1A		ALL
2053Z			CC		0-0	28-41-11		D04267J	PERG	1F		GB03102	ST..	1A		ALL
2054B	22	X2	CD		2-3	28-41-11		TB3102Y	B041	1A		D03973A	K05			ALL
2054R	22	X2	CD		0-0	28-41-11		TB3102Y	A041	1A		D03973A	J05			ALL
2054Z			CD		0-0	28-41-11		GB03102	ST..	1A		D03973A	PERG	1A		ALL
2055B	22	X2	CE		3-0	28-41-11		TB3102Y	B041	1A		D03975A	K05			ALL
2055R	22	X2	CE		0-0	28-41-11		TB3102Y	A041	1A		D03975A	J05			ALL
2055Z			CE		0-0	28-41-11		GB03102	ST..	1A		D03975A	PERG	1A		ALL
2057B	22	X2	CG		2-3	28-41-11		TB3102Y	B043	1A		D03973D	K05			ALL
2057R	22	X2	CG		0-0	28-41-11		TB3102Y	A043	1A		D03973D	J05			ALL
2057Z			CG		0-0	28-41-11		GB03102	ST..	1A		D03973D	PERG	1A		ALL
2058B	22	X2	CH		3-0	28-41-11		TB3102Y	B043	1A		D03975D	K05			ALL
2058R	22	X2	CH		0-0	28-41-11		TB3102Y	A043	1A		D03975D	J05			ALL
2058Z			CH		0-0	28-41-11		GB03102	ST..	1A		D03975D	PERG	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0311		286A0311			E3-1 ELECTRONIC SHELF - LEFT (continued)											
2060B		22		X2	CJ	2-7	28-41-11	D04267J	B02			TB3102Y	B045	1A		ALL
2060R		22		X2	CJ	0-0	28-41-11	D04267J	B01			TB3102Y	A045	1A		ALL
2060Z					CJ	0-0	28-41-11	D04267J	PERG	1F		GB03102	ST..	1A		ALL
2061B		22		X2	CK	2-4	28-41-11	TB3102Y	B045	1A		D03973B	K05			ALL
2061R		22		X2	CK	0-0	28-41-11	TB3102Y	A045	1A		D03973B	J05			ALL
2061Z					CK	0-0	28-41-11	GB03102	ST..	1A		D03973B	PERG	1A		ALL
2062B		22		X2	CL	2-10	28-41-11	TB3102Y	B045	1A		D03975B	K05			ALL
2062R		22		X2	CL	0-0	28-41-11	TB3102Y	A045	1A		D03975B	J05			ALL
2062Z					CL	0-0	28-41-11	GB03102	ST..	1A		D03975B	PERG	1A		ALL
2063B		24		Y2	CM	2-0	34-61-14	D43155J	A20			D03973B	D02			ALL
2063R		24		Y2	CM	0-0	34-61-14	D43155J	A19			D03973B	C02			ALL
2063Z					CM	0-0	34-61-14	D43155J	PERG	1F		D03973B	PERG	1A		ALL
2065B		24		Y2	CP	2-1	77-12-11	D49994J	B01			TB3102Y	B047	1A		YC051-YD157
2065B		24		Y2	CP	2-3	77-12-11	D49994J	B01			TB3102Y	B047	1A		YD158-YR328
2065R		24		Y2	CP	0-0	77-12-11	D49994J	A01			TB3102Y	A047	1A		ALL
2065Z					CP	0-0	77-12-11	D49994J	PERG	1F		GB03102	ST..	1A		ALL
2066B		24		Y2	CQ	2-5	77-12-11	TB3102Y	B047	1A		D03973A	B10			ALL
2066R		24		Y2	CQ	0-0	77-12-11	TB3102Y	A047	1A		D03973A	A10			ALL
2066Z					CQ	0-0	77-12-11	GB03102	ST..	1A		D03973A	PERG	1A		ALL
2067B		24		Y2	CR	2-11	77-12-11	TB3102Y	B047	1A		D03975A	B10			ALL
2067R		24		Y2	CR	0-0	77-12-11	TB3102Y	A047	1A		D03975A	A10			ALL
2067Z					CR	0-0	77-12-11	GB03102	ST..	1A		D03975A	PERG	1A		ALL
2068B		24		Y2	CS	2-4	77-31-11	TB3102Y	B047	1A		D40448J	A08			ALL
2068R		24		Y2	CS	0-0	77-31-11	TB3102Y	A047	1A		D40448J	B08			ALL
2068Z					CS	0-0	77-31-11	GB03102	ST..	1A		D40448J	PERG	1F		ALL
2069B		24		Y2	CT	2-4	77-12-21	D40448J	A06			TB3102Y	B049	1A		ALL
2069R		24		Y2	CT	0-0	77-12-21	D40448J	B06			TB3102Y	A049	1A		ALL
2069Z					CT	0-0	77-12-21	D40448J	PERG	1F		GB03102	ST..	1A		ALL
2070B		24		Y2	CU	2-4	77-12-21	TB3102Y	B049	1A		D03973B	B10			ALL
2070R		24		Y2	CU	0-0	77-12-21	TB3102Y	A049	1A		D03973B	A10			ALL
2070Z					CU	0-0	77-12-21	GB03102	ST..	1A		D03973B	PERG	1A		ALL
2071B		24		Y2	CV	2-10	77-12-21	TB3102Y	B049	1A		D03975B	B10			ALL
2071R		24		Y2	CV	0-0	77-12-21	TB3102Y	A049	1A		D03975B	A10			ALL
2071Z					CV	0-0	77-12-21	GB03102	ST..	1A		D03975B	PERG	1A		ALL
2072B		24		Y2	CW	2-4	77-31-11	TB3102Y	B049	1A		D40448J	A07			ALL
2072R		24		Y2	CW	0-0	77-31-11	TB3102Y	A049	1A		D40448J	B07			ALL
2072Z					CW	0-0	77-31-11	GB03102	ST..	1A		D40448J	PERG	1F		ALL
2075B		22		X2	CZ	2-2	34-33-11	D03667B	G03			TB3101Z	B017	1A		ALL
2075R		22		X2	CZ	0-0	34-33-11	D03667B	G02			TB3101Z	A017	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0311	286A0311				E3-1 ELECTRONIC SHELF - LEFT (continued)											
2075Z				CZ	0-0	34-33-11		D03667B	PERG	1A		GB03101	ST..	1A		ALL
2076B	24	Y2		DA	2-5	34-33-11		TB3101Z	B017	1A		D03973A	H15			ALL
2076R	24	Y2		DA	0-0	34-33-11		TB3101Z	A017	1A		D03973A	G15			ALL
2076Z				DA	0-0	34-33-11		GB03101	ST..	1A		D03973A	PERG	1A		ALL
2077B	24	Y2		DB	3-5	34-33-11		TB3101Z	B017	1A		D03975A	H15			ALL
2077R	24	Y2		DB	0-0	34-33-11		TB3101Z	A017	1A		D03975A	G15			ALL
2077Z				DB	0-0	34-33-11		GB03101	ST..	1A		D03975A	PERG	1A		ALL
2078B	24	Y2		DC	2-1	34-33-11		TB3101Z	B017	1A		D45111J	B07			ALL
2078R	24	Y2		DC	0-0	34-33-11		TB3101Z	A017	1A		D45111J	A07			ALL
2078Z				DC	0-0	34-33-11		GB03101	ST..	1A		D45111J	PERG	1F		ALL
2079B	24	Y2		DD	2-3	34-33-11		TB3101Z	B017	1A		D43145J	A16			ALL
2079R	24	Y2		DD	0-0	34-33-11		TB3101Z	A017	1A		D43145J	A15			ALL
2079Z				DD	0-0	34-33-11		GB03101	ST..	1A		D43145J	PERG	1F		ALL
2081B	22	X2		DF	2-0	34-57-11		D03651B	B14			TB3101Y	B021	1A		ALL
2081R	22	X2		DF	0-0	34-57-11		D03651B	B13			TB3101Y	A021	1A		ALL
2081Z				DF	0-0	34-57-11		D03651B	PERG	1A		GB03101	ST..	1A		ALL
2082B	24	Y2		DG	2-4	34-57-11		TB3101Y	B021	1A		D03973A	D03			ALL
2082R	24	Y2		DG	0-0	34-57-11		TB3101Y	A021	1A		D03973A	C03			ALL
2082Z				DG	0-0	34-57-11		GB03101	ST..	1A		D03973A	PERG	1A		ALL
2083B	24	Y2		DH	3-4	34-57-11		TB3101Y	B021	1A		D03975A	D03			ALL
2083R	24	Y2		DH	0-0	34-57-11		TB3101Y	A021	1A		D03975A	C03			ALL
2083Z				DH	0-0	34-57-11		GB03101	ST..	1A		D03975A	PERG	1A		ALL
2085B	24	Y2		DJ	2-0	31-35-02		D45111J	B12			TB3101Y	B023	1A		ALL
2085R	24	Y2		DJ	0-0	31-35-02		D45111J	A12			TB3101Y	A023	1A		ALL
2085Z				DJ	0-0	31-35-02		D45111J	PERG	1F		GB03101	ST..	1A		ALL
2086B	24	Y2		DK	2-7	31-35-02		TB3101Y	B023	1A		D03973D	D05			ALL
2086R	24	Y2		DK	0-0	31-35-02		TB3101Y	A023	1A		D03973D	C05			ALL
2086Z				DK	0-0	31-35-02		GB03101	ST..	1A		D03973D	PERG	1A		ALL
2087B	24	Y2		DL	3-4	31-35-02		TB3101Y	B023	1A		D03975D	D05			ALL
2087R	24	Y2		DL	0-0	31-35-02		TB3101Y	A023	1A		D03975D	C05			ALL
2087Z				DL	0-0	31-35-02		GB03101	ST..	1A		D03975D	PERG	1A		ALL
2089B	24	Y2		DN	2-1	22-11-51		D43145J	B08			D03973A	D12			ALL
2089R	24	Y2		DN	0-0	22-11-51		D43145J	B07			D03973A	C12			ALL
2089Z				DN	0-0	22-11-51		D43145J	PERG	1F		D03973A	PERG	1A		ALL
2090B	24	Y2		DP	2-10	22-11-51		D43145J	B10			D03975A	D12			ALL
2090R	24	Y2		DP	0-0	22-11-51		D43145J	B09			D03975A	C12			ALL
2090Z				DP	0-0	22-11-51		D43145J	PERG	1F		D03975A	PERG	1A		ALL
2091B	24	Y2		DQ	2-4	27-32-12		D45111J	B13			D03973A	H01			ALL
2091R	24	Y2		DQ	0-0	27-32-12		D45111J	A13			D03973A	G01			ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To			Effectivity				
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type		Splice	Equip	Term	Type
W0311	286A0311			E3-1 ELECTRONIC SHELF - LEFT (continued)											
2091Z				DQ	0-0	27-32-12	D45111J	PERG	1F		D03973A	PERG	1A		ALL
2092B	24	Y2	DR		3-4	27-32-12	D45111J	B15			D03975A	H01			ALL
2092R	24	Y2	DR		0-0	27-32-12	D45111J	A15			D03975A	G01			ALL
2092Z			DR		0-0	27-32-12	D45111J	PERG	1F		D03975A	PERG	1A		ALL
2093B	24	Y2	DS		2-1	34-55-11	D45111J	B10			TB3101Y	B025	1A		ALL
2093R	24	Y2	DS		0-0	34-55-11	D45111J	A10			TB3101Y	A025	1A		ALL
2093Z			DS		0-0	34-55-11	D45111J	PERG	1F		GB03101	ST..	1A		ALL
2094B	24	Y2	DT		2-4	34-55-11	TB3101Y	B025	1A		D03973B	D09			ALL
2094R	24	Y2	DT		0-0	34-55-11	TB3101Y	A025	1A		D03973B	C09			ALL
2094Z			DT		0-0	34-55-11	GB03101	ST..	1A		D03973B	PERG	1A		ALL
2095B	24	Y2	DU		3-4	34-55-11	TB3101Y	B025	1A		D03975B	D09			ALL
2095R	24	Y2	DU		0-0	34-55-11	TB3101Y	A025	1A		D03975B	C09			ALL
2095Z			DU		0-0	34-55-11	GB03101	ST..	1A		D03975B	PERG	1A		ALL
2096B	24	Y2	DV		2-2	34-31-11	D45111J	B03			TB3101Z	B029	1A		ALL
2096R	24	Y2	DV		0-0	34-31-11	D45111J	A03			TB3101Z	A029	1A		ALL
2096Z			DV		0-0	34-31-11	D45111J	PERG	1F		GB03101	ST..	1A		ALL
2097B	24	Y2	DW		2-1	34-31-11	TB3101Z	B029	1A		D03973A	D15			ALL
2097R	24	Y2	DW		0-0	34-31-11	TB3101Z	A029	1A		D03973A	C15			ALL
2097Z			DW		0-0	34-31-11	GB03101	ST..	1A		D03973A	PERG	1A		ALL
2098B	24	Y2	DX		2-3	34-31-11	TB3101Z	B029	1A		D03973E	H03			ALL
2098R	24	Y2	DX		0-0	34-31-11	TB3101Z	A029	1A		D03973E	G03			ALL
2098Z			DX		0-0	34-31-11	GB03101	ST..	1A		D03973E	PERG	1A		ALL
2099B	24	Y2	DY		3-1	34-31-11	TB3101Z	B029	1A		D03975A	D15			ALL
2099R	24	Y2	DY		0-0	34-31-11	TB3101Z	A029	1A		D03975A	C15			ALL
2099Z			DY		0-0	34-31-11	GB03101	ST..	1A		D03975A	PERG	1A		ALL
2100B	24	Y2	DZ		3-0	34-31-11	TB3101Z	B029	1A		D03975E	H03			ALL
2100R	24	Y2	DZ		0-0	34-31-11	TB3101Z	A029	1A		D03975E	G03			ALL
2100Z			DZ		0-0	34-31-11	GB03101	ST..	1A		D03975E	PERG	1A		ALL
2101B	24	Y2	EA		2-3	34-51-11	D45111J	B05			D03973B	D03			ALL
2101R	24	Y2	EA		0-0	34-51-11	D45111J	A05			D03973B	C03			ALL
2101Z			EA		0-0	34-51-11	D45111J	PERG	1F		D03973B	PERG	1A		ALL
2102B	24	Y2	EB		3-3	34-51-11	D45111J	B06			D03975B	D03			ALL
2102R	24	Y2	EB		0-0	34-51-11	D45111J	A06			D03975B	C03			ALL
2102Z			EB		0-0	34-51-11	D45111J	PERG	1F		D03975B	PERG	1A		ALL
2103B	22	X2	EC		1-11	34-61-15	D43155J	B04			TB3101Y	B035	1A		ALL
2103R	22	X2	EC		0-0	34-61-15	D43155J	B03			TB3101Y	A035	1A		ALL
2103Z			EC		0-0	34-61-15	D43155J	PERG	1F		GB03101	ST..	1A		ALL
2104B	22	X2	ED		2-1	34-61-15	TB3101Y	B035	1A		D03973A	D09			ALL
2104R	22	X2	ED		0-0	34-61-15	TB3101Y	A035	1A		D03973A	C09			ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0311	286A0311				E3-1 ELECTRONIC SHELF - LEFT (continued)											
2104Z				ED	0-0	34-61-15		GB03101	ST..	1A		D03973A	PERG	1A		ALL
2105B	22	X2		EE	3-1	34-61-15		TB3101Y	B035	1A		D03975A	D09			ALL
2105R	22	X2		EE	0-0	34-61-15		TB3101Y	A035	1A		D03975A	C09			ALL
2105Z				EE	0-0	34-61-15		GB03101	ST..	1A		D03975A	PERG	1A		ALL
2106B	22	X2		EF	1-9	34-61-15		D43155J	B06			TB3101Y	B037	1A		ALL
2106R	22	X2		EF	0-0	34-61-15		D43155J	B05			TB3101Y	A037	1A		ALL
2106Z				EF	0-0	34-61-15		D43155J	PERG	1F		GB03101	ST..	1A		ALL
2107B	22	X2		EG	2-1	34-61-15		TB3101Y	B037	1A		D03973E	D01			ALL
2107R	22	X2		EG	0-0	34-61-15		TB3101Y	A037	1A		D03973E	C01			ALL
2107Z				EG	0-0	34-61-15		GB03101	ST..	1A		D03973E	PERG	1A		ALL
2108B	22	X2		EH	2-10	34-61-15		TB3101Y	B037	1A		D03975E	D01			ALL
2108R	22	X2		EH	0-0	34-61-15		TB3101Y	A037	1A		D03975E	C01			ALL
2108Z				EH	0-0	34-61-15		GB03101	ST..	1A		D03975E	PERG	1A		ALL
2109B	22	X2		EI	1-9	34-61-18		D43155J	B08			TB3101Y	B041	1A		YC051-YC058
2109B	22	X2		EI	1-9	31-32-15		D43155J	B08			TB3101Y	B041	1A		YC059-YR328
2109R	22	X2		EI	0-0	34-61-18		D43155J	B07			TB3101Y	A041	1A		YC051-YC058
2109R	22	X2		EI	0-0	31-32-15		D43155J	B07			TB3101Y	A041	1A		YC059-YR328
2109Z				EI	0-0	34-61-18		D43155J	PERG	1F		GB03101	ST..	1A		YC051-YC058
2109Z				EI	0-0	31-32-15		D43155J	PERG	1F		GB03101	ST..	1A		YC059-YR328
2110B	22	X2		EJ	2-2	34-61-18		TB3101Y	B041	1A		D03973A	F15			YC051-YC058
2110B	22	X2		EJ	2-2	31-32-15		TB3101Y	B041	1A		D03973A	F15			YC059-YR328
2110R	22	X2		EJ	0-0	34-61-18		TB3101Y	A041	1A		D03973A	E15			YC051-YC058
2110R	22	X2		EJ	0-0	31-32-15		TB3101Y	A041	1A		D03973A	E15			YC059-YR328
2110Z				EJ	0-0	34-61-18		GB03101	ST..	1A		D03973A	PERG	1A		YC051-YC058
2110Z				EJ	0-0	31-32-15		GB03101	ST..	1A		D03973A	PERG	1A		YC059-YR328
2111B	22	X2		EK	2-11	34-61-18		TB3101Y	B041	1A		D03975A	F15			YC051-YC058
2111R	22	X2		EK	0-0	34-61-18		TB3101Y	A041	1A		D03975A	E15			YC051-YC058
2111Z				EK	0-0	34-61-18		GB03101	ST..	1A		D03975A	PERG	1A		YC051-YC058
2112B	22	X2		EL	2-3	34-61-18		TB3101Y	B041	1A		D45111J	B11			YC051-YC058
2112B	22	X2		EL	2-3	31-32-15		TB3101Y	B041	1A		D45111J	B11			YC059-YR328
2112R	22	X2		EL	0-0	34-61-18		TB3101Y	A041	1A		D45111J	A11			YC051-YC058
2112R	22	X2		EL	0-0	31-32-15		TB3101Y	A041	1A		D45111J	A11			YC059-YR328
2112Z				EL	0-0	34-61-18		GB03101	ST..	1A		D45111J	PERG	1F		YC051-YC058
2112Z				EL	0-0	31-32-15		GB03101	ST..	1A		D45111J	PERG	1F		YC059-YR328
2115B	24	Y2		EP	2-0	34-21-13		D43155J	A08			D03973A	D02			ALL
2115R	24	Y2		EP	0-0	34-21-13		D43155J	A07			D03973A	C02			ALL
2115Z				EP	0-0	34-21-13		D43155J	PERG	1F		D03973A	PERG	1A		ALL
2116B	24	Y2		EQ	2-10	34-21-13		D43155J	A06			D03975A	D02			YC051-YC052
2116B	24	Y2		EQ	3-3	34-21-13		SP00508		W		D03975A	D02			YC053-YR328

WIRE LIST

D280A108

91-21-11

Section W0310

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To				Effectivity			
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type	Splice		Equip	Term	Type
W0311	286A0311			E3-1 ELECTRONIC SHELF - LEFT (continued)											
2116R	24	Y2	EQ		0-0	34-21-13	D43155J	A05			D03975A	C02			YC051-YC052
2116R	24	Y2	EQ		0-0	34-21-13	SP00507		W		D03975A	C02			YC053-YR328
2116Z			EQ		0-0	34-21-13	D43155J	PERG	1F		D03975A	PERG	1A		YC051-YC052
2116Z			EQ		0-0	34-21-13	SP00509		W		D03975A	PERG	1A		YC053-YR328
2117B	24	Y2	ER		1-10	34-21-14	D43145J	A14			TB3101Y	B043	1A		ALL
2117R	24	Y2	ER		0-0	34-21-14	D43145J	A13			TB3101Y	A043	1A		ALL
2117Z			ER		0-0	34-21-14	D43145J	PERG	1F		GB03101	ST..	1A		ALL
2118B	24	Y2	ES		2-1	34-21-14	TB3101Y	B043	1A		D03973B	D05			ALL
2118R	24	Y2	ES		0-0	34-21-14	TB3101Y	A043	1A		D03973B	C05			ALL
2118Z			ES		0-0	34-21-14	GB03101	ST..	1A		D03973B	PERG	1A		ALL
2119B	24	Y2	ET		2-2	34-21-14	TB3101Y	B043	1A		D03973D	F05			ALL
2119R	24	Y2	ET		0-0	34-21-14	TB3101Y	A043	1A		D03973D	E05			ALL
2119Z			ET		0-0	34-21-14	GB03101	ST..	1A		D03973D	PERG	1A		ALL
2120B	24	Y2	EU		1-11	34-21-14	D43145J	A12			TB3101Y	B045	1A		ALL
2120R	24	Y2	EU		0-0	34-21-14	D43145J	A11			TB3101Y	A045	1A		ALL
2120Z			EU		0-0	34-21-14	D43145J	PERG	1F		GB03101	ST..	1A		ALL
2121B	24	Y2	EV		2-9	34-21-14	TB3101Y	B045	1A		D03975B	D05			ALL
2121R	24	Y2	EV		0-0	34-21-14	TB3101Y	A045	1A		D03975B	C05			ALL
2121Z			EV		0-0	34-21-14	GB03101	ST..	1A		D03975B	PERG	1A		ALL
2122B	24	Y2	EW		2-10	34-21-14	TB3101Y	B045	1A		D03975D	F05			ALL
2122R	24	Y2	EW		0-0	34-21-14	TB3101Y	A045	1A		D03975D	E05			ALL
2122Z			EW		0-0	34-21-14	GB03101	ST..	1A		D03975D	PERG	1A		ALL
2123B	24	Y2	EX		2-9	79-31-11	TB3102Z	B053	1A		D03973A	F14			ALL
2123R	24	Y2	EX		0-0	79-31-11	TB3102Z	A053	1A		D03973A	E14			ALL
2123Z			EX		0-0	79-31-11	GB03102	ST..	1A		D03973A	PERG	1A		ALL
2124B	24	Y2	EY		2-8	79-31-11	TB3102Z	B053	1A		D03973B	B06			ALL
2124R	24	Y2	EY		0-0	79-31-11	TB3102Z	A053	1A		D03973B	A06			ALL
2124Z			EY		0-0	79-31-11	GB03102	ST..	1A		D03973B	PERG	1A		ALL
2125B	24	Y2	EZ		2-7	79-31-11	TB3102Z	B053	1A		D03975A	F14			ALL
2125R	24	Y2	EZ		0-0	79-31-11	TB3102Z	A053	1A		D03975A	E14			ALL
2125Z			EZ		0-0	79-31-11	GB03102	ST..	1A		D03975A	PERG	1A		ALL
2126B	24	Y2	FA		2-7	79-31-11	TB3102Z	B053	1A		D03975B	B06			ALL
2126R	24	Y2	FA		0-0	79-31-11	TB3102Z	A053	1A		D03975B	A06			ALL
2126Z			FA		0-0	79-31-11	GB03102	ST..	1A		D03975B	PERG	1A		ALL
2127B	22	X2	FB		2-1	22-23-12	D04267J	A18			D45111J	B14			YC051-YL959, YN231-YN235
2127B	22	X2	FB		2-1	SPARE	D04267J	A18			D45111J	B14			YL963-YL999, YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W0310

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0311	286A0311			E3-1 ELECTRONIC SHELF - LEFT (continued)											
2127R	22	X2	FB		0-0	22-23-12	D04267J	A17			D45111J	A14			YC051-YL959, YN231-YN235
2127R	22	X2	FB		0-0	SPARE	D04267J	A17			D45111J	A14			YL963-YL999, YN236-YR328
2127Z			FB		0-0	22-23-12	D04267J	PERG	1F		D45111J	PERG	1F		YC051-YL959, YN231-YN235
2127Z			FB		0-0	SPARE	D04267J	PERG	1F		D45111J	PERG	1F		YL963-YL999, YN236-YR328
2128B	24	Y2	FC		2-7	34-57-11	D42005J	A03			D03651B	B08			YC051-YD157
2128B	24	Y2	FC		2-8	34-57-11	D42005J	A03			D03651B	B08			YD158-YR328
2128R	24	Y2	FC		0-0	34-57-11	D42005J	A02			D03651B	B07			ALL
2128Z			FC		0-0	34-57-11	D42005J	PERG	1F		D03651B	PERG	1A		ALL
2129B	24	Y2	FD		2-2	34-57-11	D03651B	B11			D45111J	B16			ALL
2129R	24	Y2	FD		0-0	34-57-11	D03651B	B10			D45111J	A16			ALL
2129Z			FD		0-0	34-57-11	D03651B	PERG	1A		D45111J	PERG	1F		ALL
2130B	24	M5	FE		2-1	34-57-11	D03651B	B02			D04271J	B01			ALL
2130R	24	M5	FE		0-0	34-57-11	D03651B	B01			D04271J	A01			ALL
2130ZI			FE		0-0	34-57-11	D03651B	DED			D04271J	A02			ALL
2130ZO			FE		0-0	34-57-11	D03651B	PERG	1A		D04271J	PERG	1F		ALL
2131B	24	Y2	FF		2-0	34-57-11	D42163J	A02			D03651B	D02			ALL
2131R	24	Y2	FF		0-0	34-57-11	D42163J	A01			D03651B	D01			ALL
2131Z			FF		0-0	34-57-11	D42163J	PERG	1F		D03651B	PERG	1A		ALL
2132B	24	Y2	FG		2-0	34-57-11	D42163J	A04			D03651B	D08			ALL
2132R	24	Y2	FG		0-0	34-57-11	D42163J	A03			D03651B	D07			ALL
2132Z			FG		0-0	34-57-11	D42163J	PERG	1F		D03651B	PERG	1A		ALL
2133B	24	Y2	FH		2-0	34-57-11	D42163J	A06			D03651B	D15			ALL
2133R	24	Y2	FH		0-0	34-57-11	D42163J	A05			D03651B	D14			ALL
2133Z			FH		0-0	34-57-11	D42163J	PERG	1F		D03651B	PERG	1A		ALL
2134B	22	X2	FI		2-0	34-57-11	D03651B	C11			D42163J	A08			ALL
2134R	22	X2	FI		0-0	34-57-11	D03651B	C10			D42163J	A07			ALL
2134Z			FI		0-0	34-57-11	D03651B	PERG	1A		D42163J	PERG	1F		ALL
2135B	24	Y2	FJ		2-7	34-33-11	D03667B	B03			D43145J	A02			ALL
2135R	24	Y2	FJ		0-0	34-33-11	D03667B	B02			D43145J	A01			ALL
2135Z			FJ		0-0	34-33-11	D03667B	PERG	1A		D43145J	PERG	1F		ALL
2136B	24	Y2	FK		2-5	34-45-11	D45111J	B09			TB3101Y	B049	1A		ALL
2136R	24	Y2	FK		0-0	34-45-11	D45111J	A09			TB3101Y	A049	1A		ALL
2136Z			FK		0-0	34-45-11	D45111J	PERG	1F		GB03101	ST..	1A		ALL
2137B	24	Y2	FL		2-4	34-45-11	TB3101Y	B049	1A		D03973A	K02			ALL
2137R	24	Y2	FL		0-0	34-45-11	TB3101Y	A049	1A		D03973A	J02			ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To			Effectivity				
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type		Splice	Equip	Term	Type
W0311	286A0311			E3-1 ELECTRONIC SHELF - LEFT (continued)											
2137Z				FL	0-0	34-45-11	GB03101	ST..	1A		D03973A	PERG	1A		ALL
2138B	24	Y2	FM		2-10	34-45-11	TB3101Y	B049	1A		D03975A	K02			ALL
2138R	24	Y2	FM		0-0	34-45-11	TB3101Y	A049	1A		D03975A	J02			ALL
2138Z			FM		0-0	34-45-11	GB03101	ST..	1A		D03975A	PERG	1A		ALL
2139B	24	M5	FN		2-5	34-49-11	D43145J	A19			D04271J	B04			ALL
2139R	24	M5	FN		0-0	34-49-11	D43145J	A18			D04271J	A04			ALL
2139ZI			FN		0-0	34-49-11	D43145J	A20			D04271J	A05			ALL
2139ZO			FN		0-0	34-49-11	D43145J	PERG	1F		D04271J	PERG	1F		ALL
2142B	24	Y2	FR		2-2	34-41-11	D04267J	B06			TB3101Z	B017	1A		YC051-YC052
2142R	24	Y2	FR		0-0	34-41-11	D04267J	B05			TB3101Z	A017	1A		YC051-YC052
2142Z			FR		0-0	34-41-11	D04267J	PERG	1F		GB03101	ST..	1A		YC051-YC052
2143B	24	7K	FS		2-10	34-41-11	D04267J	A12			TB3101Z	B053	1A		YC051-YC052
2143W	24	7K	FS		0-0	34-41-11	D04267J	A11			TB3101Z	A053	1A		YC051-YC052
2143Z			FS		0-0	34-41-11	D04267J	PERG	1F		GB03101	ST..	1A		YC051-YC052
2144B	24	7K	FT		2-2	34-41-11	TB3101Z	B053	1A		D03973F	K01			ALL
2144W	24	7K	FT		0-0	34-41-11	TB3101Z	A053	1A		D03973F	J01			ALL
2144Z			FT		0-0	34-41-11	GB03101	ST..	1A		D03973F	DED			ALL
2145B	24	7K	FU		2-2	34-41-11	TB3101Z	B057	1A		D03973F	B01			ALL
2145W	24	7K	FU		0-0	34-41-11	TB3101Z	A057	1A		D03973F	A01			ALL
2145Z			FU		0-0	34-41-11	GB03101	ST..	1A		D03973F	DED			ALL
2149B	24	Y2	FY		2-1	22-11-51	D43145J	B06			D03973A	F05			ALL
2149R	24	Y2	FY		0-0	22-11-51	D43145J	B05			D03973A	E05			ALL
2149Z			FY		0-0	22-11-51	D43145J	PERG	1F		D03973A	PERG	1A		ALL
2150B	24	Y2	FZ		2-10	22-11-51	D43145J	B04			D03975A	F05			ALL
2150R	24	Y2	FZ		0-0	22-11-51	D43145J	B03			D03975A	E05			ALL
2150Z			FZ		0-0	22-11-51	D43145J	PERG	1F		D03975A	PERG	1A		ALL
2151B	24	Y2	GA		3-2	31-62-25	D03975D	K15			D45151J	B05			YC051-YD157
2151R	24	Y2	GA		0-0	31-62-25	D03975D	J15			D45151J	A05			YC051-YD157
2151Z			GA		0-0	31-62-25	D03975D	PERG	1A		D45151J	PERG	1F		YC051-YD157
2155B	24	Y6	GE		1-11	31-35-02	TB3101Y	B023	1A		D45151J	B08			YC051-YD157
2155B	24	Y2	GE		1-11	31-35-02	TB3101Y	B023	1A		D45151J	B08			YD158-YR328
2155R	24	Y6	GE		0-0	31-35-02	TB3101Y	A023	1A		D45151J	A08			YC051-YD157
2155R	24	Y2	GE		0-0	31-35-02	TB3101Y	A023	1A		D45151J	A08			YD158-YR328
2155Z			GE		0-0	31-35-02	D45151J	PERG	1F		GB03101	ST..	1A		YC051-YD157
2155Z			GE		0-0	31-35-02	GB03101	ST..	1A		D45151J	PERG	1F		YD158-YR328
2156B	24	Y2	GF		2-1	27-81-41	D45131J	B19			TB3101Y	B033	1A		ALL
2156R	24	Y2	GF		0-0	27-81-41	D45131J	A19			TB3101Y	A033	1A		ALL
2156Z			GF		0-0	27-81-41	D45131J	PERG	1F		GB03101	ST..	1A		ALL
2157B	24	Y2	GG		2-3	27-81-41	TB3101Y	B033	1A		D03973E	F01			ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0311	286A0311			E3-1 ELECTRONIC SHELF - LEFT (continued)											
2157R	24	Y2	GG		0-0	27-81-41	TB3101Y	A033	1A		D03973E	E01			ALL
2157Z			GG		0-0	27-81-41	GB03101	ST..	1A		D03973E	PERG	1A		ALL
2158B	24	Y2	GH		2-0	34-58-11	D45131J	B06			D04267J	B08			YC053-YR328
2158R	24	Y2	GH		0-0	34-58-11	D45131J	A06			D04267J	B07			YC053-YR328
2158Z			GH		0-0	34-58-11	D45131J	PERG	1F		D04267J	PERG	1F		YC053-YR328
2159B	24	Y2	GI		2-2	23-27-38	D45151J	B06			TB3101Y	B039	1A		YD158-YR328
2159R	24	Y2	GI		0-0	23-27-38	D45151J	A06			TB3101Y	A039	1A		YD158-YR328
2159Z			GI		0-0	23-27-38	D45151J	PERG	1F		GB03101	ST..	1A		YD158-YR328
2160B	24	Y2	GJ		2-2	23-27-38	D03973D	K15			TB3101Y	B039	1A		YD158-YD170, YL968-YL999, YN236-YN260
2160B	24	Y2	GJ		2-2	23-27-38	TB3101Y	B039	1A		D03973D	K15			YL951-YL967, YN231-YN235, YN501-YR328
2160R	24	Y2	GJ		0-0	23-27-38	D03973D	J15			TB3101Y	A039	1A		YD158-YD170, YL968-YL999, YN236-YN260
2160R	24	Y2	GJ		0-0	23-27-38	TB3101Y	A039	1A		D03973D	J15			YL951-YL967, YN231-YN235, YN501-YR328
2160Z			GJ		0-0	23-27-38	D03973D	PERG	1A		GB03101	ST..	1A		YD158-YD170, YL968-YL999, YN236-YN260
2160Z			GJ		0-0	23-27-38	GB03101	ST..	1A		D03973D	PERG	1A		YL951-YL967, YN231-YN235, YN501-YR328
2161B	24	Y2	GK		2-11	23-27-38	D03975D	K15			TB3101Y	B039	1A		YD158-YD170, YL968-YL999, YN236-YN260
2161B	24	Y2	GK		2-11	23-27-38	TB3101Y	B039	1A		D03975D	K15			YL951-YL967, YN231-YN235, YN501-YR328
2161R	24	Y2	GK		0-0	23-27-38	D03975D	J15			TB3101Y	A039	1A		YD158-YD170, YL968-YL999, YN236-YN260
2161R	24	Y2	GK		0-0	23-27-38	TB3101Y	A039	1A		D03975D	J15			YL951-YL967, YN231-YN235, YN501-YR328

WIRE LIST
D280A108

91-21-11
Section W0310
Page 18
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0311	286A0311			E3-1 ELECTRONIC SHELF - LEFT (continued)											
2161Z				GK	0-0	23-27-38	D03975D	PERG	1A		GB03101	ST..	1A		YD158-YD170, YL968-YL999, YN236-YN260
2161Z				GK	0-0	23-27-38	GB03101	ST..	1A		D03975D	PERG	1A		YL951-YL967, YN231-YN235, YN501-YR328
2162B	22	X2	GL		2-3	49-62-11	TB3102Z	B057	1A		D43155J	B18			ALL
2162R	22	X2	GL		0-0	49-62-11	TB3102Z	A057	1A		D43155J	B17			ALL
2162Z			GL		0-0	49-62-11	GB03102	ST..	1A		D43155J	PERG	1F		ALL
2163B	24	Y2	GM		2-0	31-62-15	SM00015		W		D45151J	B03			YL951-YR328
2163R	24	Y2	GM		0-0	31-62-15	SM00014		W		D45151J	A03			YL951-YR328
2163Z			GM		0-0	31-62-15	SM00013		W		D45151J	PERG	1F		YL951-YR328
2164B	24	Y2	GN		2-0	31-62-15	SM00018		W		D45151J	B04			YL951-YR328
2164R	24	Y2	GN		0-0	31-62-15	SM00017		W		D45151J	A04			YL951-YR328
2164Z			GN		0-0	31-62-15	SM00016		W		D45151J	PERG	1F		YL951-YR328
2165B	24	Y2	GP		2-1	31-62-15	SM00015		W		D45131J	B15			YL951-YR328
2165R	24	Y2	GP		0-0	31-62-15	SM00014		W		D45131J	A15			YL951-YR328
2165Z			GP		0-0	31-62-15	SM00013		W		D45131J	PERG	1F		YL951-YR328
2166B	24	Y2	GQ		2-1	31-62-15	SM00018		W		D45131J	B16			YL951-YR328
2166R	24	Y2	GQ		0-0	31-62-15	SM00017		W		D45131J	A16			YL951-YR328
2166Z			GQ		0-0	31-62-15	SM00016		W		D45131J	PERG	1F		YL951-YR328
2169B	24	Y2	GT		3-1	34-21-13	SP00508		W		D43155J	A06			YC053-YR328
2169R	24	Y2	GT		0-0	34-21-13	SP00507		W		D43155J	A05			YC053-YR328
2169Z			GT		0-0	34-21-13	SP00509		W		D43155J	PERG	1F		YC053-YR328
2171B	24	Y2	HA		3-7	31-62-15	D45131J	B14			SP00159		W		YC053-YR328
2171R	24	Y2	HA		0-0	31-62-15	D45131J	A14			SP00157		W		YC053-YR328
2171Z			HA		0-0	31-62-15	D45131J	PERG	1F		SP00161		W		YC053-YR328
3001B	24	Y3	XA		2-5	79-31-11	D49994J	A03			TB3102Z	B053	1A		YC051-YD157
3001B	24	Y3	XA		2-6	79-31-11	D49994J	A03			TB3102Z	B053	1A		YD158-YR328
3001R	24	Y3	XA		0-0	79-31-11	D49994J	A02			TB3102Z	A053	1A		ALL
3001Y	24	Y3	XA		0-0	79-31-11	D49994J	B02			TB3102Y	B051	1A		ALL
3001Z			XA		0-0	79-31-11	D49994J	PERG	1F		GB03102	ST..	1A		ALL
301CO			ZB		0-0	31-62-12	D03975C	= 13			D40301J	= C1			ALL
301CX		0F	ZB		2-5	31-62-12	D03975C	13	DN		D40301J	= A1			ALL
W0313	286A0313			E3-1 ELECTRONIC SHELF - RIGHT											
0003	22	PA			3-1	30-31-12	D03975E	F12			SP00891		W		YL968-YL999, YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W0310

Page 19

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From			To					
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0313	286A0313			E3-1 ELECTRONIC SHELF - RIGHT (continued)											
0004	22		PA		3-1	30-31-12	D03975B	F12			SP00889		W		YL968-YL999, YN236-YR328
0005	22		PA		3-4	30-31-12	D04297J	B08			SP00889		W		YL968-YL999, YN236-YR328
0006	22		PA		3-4	30-31-12	D04297J	B15			SP00891		W		YL968-YL999, YN236-YR328
0502	16		CQ		2-2	31-62-21	D03975C	2			D46035J	7			ALL
0503	14		CQ		1-11	31-62-21	D03975C	7			GD03975	DC..	E		ALL
0504	16		CQ		2-2	31-62-21	D03975C	10			D46035J	4			ALL
0505	14		CQ		1-11	31-62-21	D03975C	8			GD03975	DC..	E		ALL
0510	16		PA		1-9	31-62-21	D03975C	9			GD03104	ST..	1		ALL
0511	16		PA		1-9	31-62-21	D03975C	3			GD03104	ST..	1		ALL
0512	24		PK		2-1	31-62-24	D40732J	A16			TB3102Y	B103	1A		YC051-YD157
0512	24		PK		2-3	31-62-24	D40732J	A16			TB3102Y	B103	1A		YD158-YR328
0513	24		PK		3-2	31-62-24	TB3102Y	B103	1A		D03973D	A11			ALL
0514	24		PK		2-6	31-62-24	TB3102Y	B103	1A		D03975D	A11			ALL
0515	24		PK		2-6	31-62-24	D03973D	H09			TB3102Y	A065	1A		ALL
0516	24		PK		2-6	31-62-24	D03975D	H09			TB3102Y	A065	1A		ALL
0517	24		PK		2-7	31-62-24	TB3102Y	A065	1A		D40394J	A17			ALL
0518	24		PK		2-0	31-62-25	D03975A	H08			D43157J	B11			ALL
0519	24		PK		2-0	31-62-25	D03975A	E08			D43157J	B12			ALL
0520	24		PK		2-0	31-62-25	D03975A	B08			D43157J	B13			ALL
0521	24		PK		1-8	31-62-25	SM00502		W		D03975D	H07			ALL
0522	24		PK		1-8	31-62-15	SM00502		W		D03973D	H07			ALL
0523	24		PK		1-3	31-62-25	D43157J	B02			SM00502		W		ALL
0525	22		PA		1-11	31-62-41	D03975E	F07			GD03104	DC..	1		ALL
0526	22		PA		2-0	31-62-41	D03975D	C10			GD03104	DC..	1		ALL
0527	24		G6		2-7	74-31-11	D40544J	B10			TB3102Y	B101	1A		ALL
0528	24		G6		2-5	74-31-11	D03975E	F09			TB3102Y	B101	1A		ALL
0529	24		G6		3-1	74-31-11	D03973E	F09			TB3102Y	B101	1A		ALL
0530	24		G6		2-7	74-31-11	D40544J	A10			TB3102Y	A101	1A		ALL
0531	24		G6		2-5	74-31-11	D03975E	C14			TB3102Y	A101	1A		ALL
0532	24		G6		3-1	74-31-11	D03973E	C14			TB3102Y	A101	1A		ALL
0533	24		PK		2-6	74-31-11	D40544J	B07			TB3102Y	B099	1A		ALL
0534	24		PK		2-4	74-31-11	D03975E	A07			TB3102Y	B099	1A		ALL
0535	24		G6		3-1	74-31-11	D03973E	A07			TB3102Y	B099	1A		ALL
0536	24		G6		2-2	76-21-21	D40394J	B06			TB3102Y	A097	1A		ALL
0537	24		G6		3-3	76-21-21	TB3102Y	A097	1A		D03973A	H02			ALL
0538	24		G6		3-1	76-21-21	TB3102Y	A097	1A		D03973E	H02			ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 20

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0313															
		286A0313				E3-1 ELECTRONIC SHELF - RIGHT (continued)									
	0539	24	G6		2-5	76-21-21	TB3102Y	A099	1A		D03975A	H02			ALL
	0540	24	G6		2-4	76-21-21	TB3102Y	A099	1A		D03975E	H02			ALL
	0541	24	G6		1-7	76-21-21	TB3102Y	A097	1A		TB3102Y	A099	1A		ALL
	0542	24	PK		2-6	73-21-31	D43147J	A16			TB3102Y	A095	1A		ALL
	0543	24	PK		2-6	73-21-31	D43147J	A17			TB3102Y	B095	1A		ALL
	0544	24	PK		2-6	73-21-31	D43147J	A18			TB3102Y	B097	1A		ALL
	0545	24	PK		2-4	73-21-31	TB3102Y	B097	1A		D03975E	C06			ALL
	0546	24	PK		2-4	73-21-31	TB3102Y	B095	1A		D03975E	A02			ALL
	0547	24	PK		2-4	73-21-31	TB3102Y	A095	1A		D03975E	E07			ALL
	0548	24	G6		3-0	73-21-31	TB3102Y	A095	1A		D03973E	E07			ALL
	0549	24	G6		3-0	73-21-31	TB3102Y	B095	1A		D03973E	A02			ALL
	0550	24	G6		3-1	73-21-31	TB3102Y	B097	1A		D03973E	C06			ALL
	0551	24	G6		2-6	73-21-12	D40544J	A08			TB3102Y	A093	1A		ALL
	0552	24	G6		2-4	73-21-12	TB3102Y	A093	1A		D03975E	J07			ALL
	0553	24	G6		3-0	73-21-12	TB3102Y	A093	1A		D03973E	J07			ALL
	0554	24	G6		2-1	73-22-11	D40394J	B02			TB3102Y	A091	1A		ALL
	0555	24	G6		2-3	73-22-11	TB3102Y	A091	1A		D03975E	D13			ALL
	0556	24	G6		2-11	73-22-11	TB3102Y	A091	1A		D03973E	D13			ALL
	0557	24	G6		2-2	73-22-31	D40394J	B03			TB3102Y	B093	1A		ALL
	0558	24	G6		2-5	73-22-31	TB3102Y	B093	1A		D03975D	F12			ALL
	0559	24	G6		3-1	73-22-31	TB3102Y	B093	1A		D03973D	F12			ALL
	0560	24	PK		2-5	73-23-11	D40544J	B08			TB3102Y	A089	1A		ALL
	0561	24	PK		2-1	73-23-11	D40394J	B04			TB3102Y	B091	1A		ALL
	0562	24	PK		2-1	73-23-11	D40394J	B05			TB3102Y	B089	1A		ALL
	0563	24	PK		2-3	73-23-11	TB3102Y	A089	1A		D03975E	A11			ALL
	0564	24	PK		2-3	73-23-11	TB3102Y	B089	1A		D03975E	D08			ALL
	0565	24	PK		2-4	73-23-11	TB3102Y	B091	1A		D03975D	D08			ALL
	0566	24	PK		3-1	73-23-11	TB3102Y	B091	1A		D03973D	D08			ALL
	0567	24	G6		2-11	73-23-11	TB3102Y	A089	1A		D03973E	A11			ALL
	0568	24	PK		2-11	73-23-11	TB3102Y	B089	1A		D03973E	D08			ALL
	0570	24	PK		2-9	31-62-41	TB3101Y	A047	1A		D03975A	E02			YD158-YR328
	0571	24	PK		3-2	31-62-41	TB3101Y	B047	1A		SP03103		W		YD158-YR328
	0572	24	PK		3-4	31-62-41	D45121J	A04			SP03103		W		YD158-YR328
	0575	24	G6		2-5	73-31-11	D40544J	A09			TB3102Y	A087	1A		ALL
	0576	24	G6		2-3	73-31-11	TB3102Y	A087	1A		D03975E	B14			ALL
	0577	24	G6		2-11	73-31-11	TB3102Y	A087	1A		D03973E	B14			ALL
	0578	24	G6		2-5	73-32-11	D40544J	B09			TB3102Y	B087	1A		ALL
	0579	24	G6		2-3	73-32-11	TB3102Y	B087	1A		D03975E	F02			ALL
	0580	24	G6		2-11	73-32-11	TB3102Y	B087	1A		D03973E	F02			ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 21

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From				To						
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0313	286A0313			E3-1 ELECTRONIC SHELF - RIGHT (continued)											
0581	24		B6		2-1	80-11-11	D40394J	A20			TB3102Y	A085	1A		ALL
0582	24		B6		2-1	80-11-11	D40394J	B01			TB3102Y	B085	1A		ALL
0583	24		B6		2-3	80-11-11	TB3102Y	A085	1A		D03975E	H04			ALL
0584	24		B6		2-3	80-11-11	TB3102Y	B085	1A		D03975E	K12			ALL
0585	24		B6		2-11	80-11-11	TB3102Y	A085	1A		D03973E	H04			ALL
0586	24		B6		2-11	80-11-11	TB3102Y	B085	1A		D03973E	K12			ALL
0590	24		PK		2-2	29-31-11	D40394J	B10			TB3102Z	B081	1A		ALL
0591	24		PK		2-2	29-31-11	D40394J	B09			TB3102Y	A079	1A		ALL
0592	24		PK		2-2	29-31-11	D40394J	A10			TB3102Z	A081	1A		ALL
0593	24		PK		2-11	29-31-11	TB3102Z	B081	1A		D03973D	B06			ALL
0594	24		PK		2-11	29-31-11	TB3102Z	B081	1A		D03973D	K04			ALL
0595	24		PK		2-10	29-31-11	TB3102Z	B081	1A		D03973E	F14			ALL
0596	24		PK		2-3	29-31-11	TB3102Z	B081	1A		D03975D	B06			ALL
0597	24		PK		2-3	29-31-11	TB3102Z	B081	1A		D03975D	K04			ALL
0598	24		PK		2-2	29-31-11	TB3102Z	B081	1A		D03975E	F14			ALL
0599	24		PK		3-0	29-31-11	TB3102Y	A079	1A		D03973D	J04			ALL
0600	24		PK		2-3	29-31-11	TB3102Y	A079	1A		D03975D	J04			ALL
0601	24		PK		2-11	29-31-11	TB3102Z	A081	1A		D03973D	A06			ALL
0602	24		PK		2-10	29-31-11	TB3102Z	A081	1A		D03973E	E14			ALL
0603	24		PK		2-3	29-31-11	TB3102Z	A081	1A		D03975D	A06			ALL
0604	24		PK		2-2	29-31-11	TB3102Z	A081	1A		D03975E	E14			ALL
0605	24		PK		2-1	29-32-11	D40394J	B14			D03975A	A09			ALL
0606	24		PK		2-1	29-32-11	D40394J	B15			D03975A	B09			ALL
0607	22		G5		2-3	78-36-21	D40544J	B06			D40394J	B07			ALL
0611	22		PA		1-5	34-51-41	D40544J	A06			SM00503		W		ALL
0612	22		G5		1-7	34-51-41	SM00503		W		D03973E	G10			ALL
0613	22		PA		1-7	34-51-41	SM00503		W		D03975E	G10			ALL
0614	22		PA		1-10	34-51-41	D45121J	A01			SM00504		W		ALL
0615	22		G5		1-7	34-51-41	SM00504		W		D03973E	C08			ALL
0616	22		PA		1-7	34-51-41	SM00504		W		D03975E	C08			ALL
0625	24		PK		2-5	22-31-52	D43157J	B20			D03973D	H08			ALL
0626	24		PK		2-0	22-31-52	D43157J	A05			D03975D	H08			ALL
0631	24		PK		2-11	31-62-42	D03975F	B09			SP03104		W		YL951-YR328
0632	24		PK		3-6	31-62-42	D04277J	A06			SP03104		W		YL951-YR328
0633	24		PK		1-11	31-62-25	D43157J	B01			D03975B	G07			ALL
0636	20		PA		1-11	34-61-11	D46017J	1			D43147J	A14			ALL
0637	20		PA		1-11	34-61-11	D46017J	2			D43147J	A13			ALL
0640	22		PA		2-4	27-32-21	D40544J	A02			D45121J	A02			ALL
0641	20		PA		2-1	34-57-21	D46017J	3			D42007J	A01			ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 22

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0313		286A0313			E3-1 ELECTRONIC SHELF - RIGHT (continued)											
0642		22		PA		2-6	34-57-21	D42007J	A09			D03653C	2			ALL
0643		20		PA		1-9	34-57-21	D03653C	4			GD03105	AC..	1A		ALL
0644		20		PA		1-9	34-57-21	D03653C	3			GD03105	ST..	1A		ALL
0645		22		PA		1-10	34-57-21	D03653B	C13			GD03105	DC..	1A		ALL
0646		24		PK		1-1	34-57-21	D03653B	C05			SM00501		W		ALL
0647		24		PK		1-1	34-57-21	D03653B	C08			SM00501		W		ALL
0648		24		PK		1-1	34-57-21	D03653B	C09			SM00501		W		ALL
0649		22		PA		2-3	34-57-21	D03653B	B15			D45121J	B02			ALL
0660		24		PK		2-0	34-45-11	D43147J	A05			D03975E	D04			ALL
0661		22		PA		3-4	34-41-11	D04297J	B13			SP00501		W		YC051-YC052
0661		22		PA		1-7	34-41-11	D40149J	B07			SM00510		W		YC053-YR328
0662		22		PA		1-10	34-41-11	D04297J	B14			SM00511		W		YC051-YC052
0662		22		PA		1-7	34-41-11	D40149J	B08			SM00511		W		YC053-YR328
0663		22		PA		3-1	34-41-11	D03975B	H06			SP00501		W		YC051-YC052
0663		22		PA		1-7	34-41-11	D03975B	H06			SM00510		W		YC053-YR328
0664		22		PA		1-8	34-41-11	D03975A	H06			SM00511		W		ALL
0669		22		PA		3-2	34-41-11	D03973B	H06			SP00501		W		YC051-YC052
0669		22		PA		1-8	34-41-11	D03973B	H06			SM00510		W		YC053-YR328
0670		22		PA		1-9	34-41-11	D03973A	H06			SM00511		W		ALL
0672		22		PA		1-11	31-62-41	D03975B	F07			GD03104	DC..	1		ALL
0691		24		PK		2-2	31-62-24	D40394J	A04			TB3102Y	B079	1A		ALL
0692		24		G6		3-0	31-62-24	TB3102Y	B079	1A		D03973D	A08			ALL
0693		24		PK		2-3	31-62-24	TB3102Y	B079	1A		D03975D	A08			ALL
0694		16		CQ		2-3	31-62-11	D03973C	10			D46035J	10			ALL
0698		24		PK		1-7	31-62-24	D40732J	B14			SM00512		W		YC051-YD157
0698		24		PK		1-8	31-62-24	D40732J	B14			SM00512		W		YD158-YR328
0699		24		PK		1-8	31-62-24	D03973D	K12			SM00512		W		ALL
0700		24		PK		1-8	31-62-24	D03975D	K12			SM00512		W		ALL
0701		24		PK		1-9	34-41-11	D03973A	C13			SM00005		W		YC053-YR328
0702		24		PK		1-7	34-41-11	SM00005		W		D40149J	A08			YC053-YR328
0703		24		PK		1-8	34-41-11	D03975A	C13			SM00005		W		YC053-YR328
1501		22		X1	MA	2-3	31-62-24	D40394J	A16			TB3102Y	A103	1A		ALL
1501Z					MA	0-0	31-62-24	D40394J	PERG	1F		GB03102	ST..	1A		ALL
1502		22		X1	MB	3-2	31-62-24	TB3102Y	A103	1A		D03973D	H10			ALL
1502Z					MB	0-0	31-62-24	GB03102	ST..	1A		D03973D	PERG	1A		ALL
1503		22		X1	MC	2-6	31-62-24	TB3102Y	A103	1A		D03975D	H10			ALL
1503Z					MC	0-0	31-62-24	GB03102	ST..	1A		D03975D	PERG	1A		ALL
1504		24		Y1	MD	2-6	79-31-11	TB3102Z	B061	1A		D03973E	K04			ALL
1504Z					MD	0-0	79-31-11	GB03102	ST..	1A		D03973E	PERG	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 23

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0313	286A0313				E3-1 ELECTRONIC SHELF - RIGHT (continued)										
1505	24	Y1	ME		2-5	79-31-11	TB3102Z	B061	1A		D03975E	K04			ALL
1505Z			ME		0-0	79-31-11	GB03102	ST..	1A		D03975E	PERG	1A		ALL
1506	24	Y1	MF		2-5	79-31-11	TB3102Y	B065	1A		D03973E	J04			ALL
1506Z			MF		0-0	79-31-11	GB03102	ST..	1A		D03973E	PERG	1A		ALL
1507	24	Y1	MG		2-5	79-31-11	TB3102Y	B065	1A		D03975E	J04			ALL
1507Z			MG		0-0	79-31-11	GB03102	ST..	1A		D03975E	PERG	1A		ALL
1508	22	X1	MH		2-1	34-57-21	D03653B	C12			D42165J	A09			ALL
1508Z			MH		0-0	34-57-21	D03653B	PERG	1A		D42165J	PERG	1F		ALL
1509R	20	X5	MI		1-8	26-11-21	D40732J	A19			D40394J	A18			YC051-YD157
1509R	20	X5	MI		1-10	26-11-21	D40732J	A19			D40394J	A18			YD158-YR328
1509Z			MI		0-0	26-11-21	D40732J	DED			D40394J	DED			ALL
1510R	20	X5	MJ		1-8	26-11-21	D40732J	B19			D40394J	B18			YC051-YD157
1510R	20	X5	MJ		1-10	26-11-21	D40732J	B19			D40394J	B18			YD158-YR328
1510Z			MJ		0-0	26-11-21	D40732J	DED			D40394J	DED			ALL
201CO			ZA		0-0	31-62-22	D03973C	= 13			D40201J	= C1			ALL
201CX		0F	ZA		2-4	31-62-22	D03973C	13	DN		D40201J	= A1			ALL
2111B	22	X2	FB		2-2	31-32-15	D45121J	B08			D03975A	F15			YC059-YR328
2111R	22	X2	FB		0-0	31-32-15	D45121J	A08			D03975A	E15			YC059-YR328
2111Z			FB		0-0	31-32-15	D45121J	PERG	1F		D03975A	PERG	1A		YC059-YR328
2501B	24	Y2	AA		2-2	31-62-22	D45141J	B09			TB3101Y	B103	1A		ALL
2501R	24	Y2	AA		0-0	31-62-22	D45141J	A09			TB3101Y	A103	1A		ALL
2501Z			AA		0-0	31-62-22	D45141J	PERG	1F		GB03101	ST..	1A		ALL
2502B	24	Y2	AB		2-4	31-62-22	D04297J	A02			TB3101Y	B101	1A		ALL
2502R	24	Y2	AB		0-0	31-62-22	D04297J	A01			TB3101Y	A101	1A		ALL
2502Z			AB		0-0	31-62-22	D04297J	PERG	1F		GB03101	ST..	1A		ALL
2503B	24	Y2	AC		2-4	31-62-22	D04297J	A04			TB3101Y	B099	1A		ALL
2503R	24	Y2	AC		0-0	31-62-22	D04297J	A03			TB3101Y	A099	1A		ALL
2503Z			AC		0-0	31-62-22	D04297J	PERG	1F		GB03101	ST..	1A		ALL
2504B	24	Y2	AD		3-0	31-62-22	D03973E	B01			TB3101Y	B103	1A		ALL
2504R	24	Y2	AD		0-0	31-62-22	D03973E	A01			TB3101Y	A103	1A		ALL
2504Z			AD		0-0	31-62-22	D03973E	PERG	1A		GB03101	ST..	1A		ALL
2505B	24	Y2	AE		3-1	31-62-22	D03973D	B01			TB3101Y	B101	1A		ALL
2505R	24	Y2	AE		0-0	31-62-22	D03973D	A01			TB3101Y	A101	1A		ALL
2505Z			AE		0-0	31-62-22	D03973D	PERG	1A		GB03101	ST..	1A		ALL
2506B	24	Y2	AF		3-0	31-62-22	D03973E	K15			TB3101Y	B099	1A		ALL
2506R	24	Y2	AF		0-0	31-62-22	D03973E	J15			TB3101Y	A099	1A		ALL
2506Z			AF		0-0	31-62-22	D03973E	PERG	1A		GB03101	ST..	1A		ALL
2507B	24	Y2	AG		2-5	31-62-22	D03975D	B01			TB3101Y	B101	1A		ALL
2507R	24	Y2	AG		0-0	31-62-22	D03975D	A01			TB3101Y	A101	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 24

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0313		286A0313				E3-1 ELECTRONIC SHELF - RIGHT (continued)									
	2507Z			AG	0-0	31-62-22	D03975D	PERG	1A		GB03101	ST..	1A		ALL
	2508B	24	Y2	AH	2-4	31-62-22	D03975E	B01			TB3101Y	B103	1A		ALL
	2508R	24	Y2	AH	0-0	31-62-22	D03975E	A01			TB3101Y	A103	1A		ALL
	2508Z			AH	0-0	31-62-22	D03975E	PERG	1A		GB03101	ST..	1A		ALL
	2509B	24	Y2	AI	2-4	31-62-22	D03975E	K15			TB3101Y	B099	1A		ALL
	2509R	24	Y2	AI	0-0	31-62-22	D03975E	J15			TB3101Y	A099	1A		ALL
	2509Z			AI	0-0	31-62-22	D03975E	PERG	1A		GB03101	ST..	1A		ALL
	2510B	24	Y2	AJ	2-4	31-62-23	D04297J	A10			TB3101Y	B097	1A		ALL
	2510R	24	Y2	AJ	0-0	31-62-23	D04297J	A09			TB3101Y	A097	1A		ALL
	2510Z			AJ	0-0	31-62-23	D04297J	PERG	1F		GB03101	ST..	1A		ALL
	2511B	24	Y2	AK	3-1	31-62-23	D03973D	K01			TB3101Y	B097	1A		ALL
	2511R	24	Y2	AK	0-0	31-62-23	D03973D	J01			TB3101Y	A097	1A		ALL
	2511Z			AK	0-0	31-62-23	D03973D	PERG	1A		GB03101	ST..	1A		ALL
	2512B	24	Y2	AL	2-5	31-62-23	D03975D	K01			TB3101Y	B097	1A		ALL
	2512R	24	Y2	AL	0-0	31-62-23	D03975D	J01			TB3101Y	A097	1A		ALL
	2512Z			AL	0-0	31-62-23	D03975D	PERG	1A		GB03101	ST..	1A		ALL
	2513B	24	Y2	AM	1-11	31-62-25	D03975E	B15			D43157J	B04			ALL
	2513R	24	Y2	AM	0-0	31-62-25	D03975E	A15			D43157J	B03			ALL
	2513Z			AM	0-0	31-62-25	D03975E	PERG	1A		D43157J	PERG	1F		ALL
	2514B	24	Y2	AN	2-2	31-62-25	D03975B	B15			TB3101Y	B087	1A		ALL
	2514R	24	Y2	AN	0-0	31-62-25	D03975B	A15			TB3101Y	A087	1A		ALL
	2514Z			AN	0-0	31-62-25	D03975B	PERG	1A		GB03101	ST..	1A		ALL
	2515B	24	Y2	AP	2-3	31-62-25	D43157J	B06			TB3101Y	B087	1A		ALL
	2515R	24	Y2	AP	0-0	31-62-25	D43157J	B05			TB3101Y	A087	1A		ALL
	2515Z			AP	0-0	31-62-25	D43157J	PERG	1F		GB03101	ST..	1A		ALL
	2516B	24	Y2	AQ	2-3	31-62-25	D43157J	B08			TB3101Y	B087	1A		ALL
	2516R	24	Y2	AQ	0-0	31-62-25	D43157J	B07			TB3101Y	A087	1A		ALL
	2516Z			AQ	0-0	31-62-25	D43157J	PERG	1F		GB03101	ST..	1A		ALL
	2517B	24	Y2	AR	2-4	31-62-25	D03975D	B15			TB3101Z	B093	1A		ALL
	2517R	24	Y2	AR	0-0	31-62-25	D03975D	A15			TB3101Z	A093	1A		ALL
	2517Z			AR	0-0	31-62-25	D03975D	PERG	1A		GB03101	ST..	1A		ALL
	2518B	24	Y2	AS	2-2	31-62-25	D45121J	B10			TB3101Z	B093	1A		ALL
	2518R	24	Y2	AS	0-0	31-62-25	D45121J	A10			TB3101Z	A093	1A		ALL
	2518Z			AS	0-0	31-62-25	D45121J	PERG	1F		GB03101	ST..	1A		ALL
	2519B	24	Y2	AT	2-2	31-62-25	D45121J	B11			TB3101Z	B093	1A		ALL
	2519R	24	Y2	AT	0-0	31-62-25	D45121J	A11			TB3101Z	A093	1A		ALL
	2519Z			AT	0-0	31-62-25	D45121J	PERG	1F		GB03101	ST..	1A		ALL
	2520B	24	Y2	AU	2-2	31-62-25	D45121J	B12			TB3101Z	B093	1A		ALL
	2520R	24	Y2	AU	0-0	31-62-25	D45121J	A12			TB3101Z	A093	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 25

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To
Wire No.	GA CO TY	Fam FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice Effectivity
W0313	286A0313	E3-1 ELECTRONIC SHELF - RIGHT (continued)		
2520Z		AU 0-0 31-62-25	D45121J PERG 1F	GB03101 ST.. 1A ALL
2521B	24	Y2 AV 2-2 31-62-25	D45121J B13	TB3101Z B093 1A ALL
2521R	24	Y2 AV 0-0 31-62-25	D45121J A13	TB3101Z A093 1A ALL
2521Z		AV 0-0 31-62-25	D45121J PERG 1F	GB03101 ST.. 1A ALL
2522B	24	Y2 AW 2-4 31-62-25	D43157J B10	TB3101Z B093 1A ALL
2522R	24	Y2 AW 0-0 31-62-25	D43157J B09	TB3101Z A093 1A ALL
2522Z		AW 0-0 31-62-25	D43157J PERG 1F	GB03101 ST.. 1A ALL
2523B	24	Y2 AX 2-9 31-62-25	D03975D D07	D03973B K13 ALL
2523R	24	Y2 AX 0-0 31-62-25	D03975D C07	D03973B J13 ALL
2523Z		AX 0-0 31-62-25	D03975D PERG 1A	D03973B PERG 1A ALL
2524B	24	Y2 AY 2-8 31-62-25	D03975A D07	D03973E K13 ALL
2524R	24	Y2 AY 0-0 31-62-25	D03975A C07	D03973E J13 ALL
2524Z		AY 0-0 31-62-25	D03975A PERG 1A	D03973E PERG 1A ALL
2525B	24	Y2 AZ 2-0 31-62-25	D03975D K03	D43157J B15 ALL
2525R	24	Y2 AZ 0-0 31-62-25	D03975D J03	D43157J B14 ALL
2525Z		AZ 0-0 31-62-25	D03975D PERG 1A	D43157J PERG 1F ALL
2526B	24	Y2 BA 2-2 31-62-25	D03975B D07	TB3101Y B091 1A ALL
2526R	24	Y2 BA 0-0 31-62-25	D03975B C07	TB3101Y A091 1A ALL
2526Z		BA 0-0 31-62-25	D03975B PERG 1A	GB03101 ST.. 1A ALL
2527B	24	Y2 BB 2-3 31-62-25	D43157J B17	TB3101Y B091 1A ALL
2527R	24	Y2 BB 0-0 31-62-25	D43157J B16	TB3101Y A091 1A ALL
2527Z		BB 0-0 31-62-25	D43157J PERG 1F	GB03101 ST.. 1A ALL
2529B	24	Y2 BD 2-3 31-62-25	D43157J B19	TB3101Y B091 1A ALL
2529R	24	Y2 BD 0-0 31-62-25	D43157J B18	TB3101Y A091 1A ALL
2529Z		BD 0-0 31-62-25	D43157J PERG 1F	GB03101 ST.. 1A ALL
2530B	24	Y2 BE 2-1 31-62-25	D03975B K10	D45121J B14 YC051-YD170
2530B	24	Y2 BE 1-7 31-62-25	D03975B K10	SM00515 W YL951-YR328
2530R	24	Y2 BE 0-0 31-62-25	D03975B J10	D45121J A14 YC051-YD170
2530R	24	Y2 BE 0-0 31-62-25	D03975B J10	SM00514 W YL951-YR328
2530Z		BE 0-0 31-62-25	D03975B PERG 1A	D45121J PERG 1F YC051-YD170
2530Z		BE 0-0 31-62-25	D03975B PERG 1A	SM00513 W YL951-YR328
2531B	24	Y2 BF 2-2 31-62-25	D03975E K10	D45121J B15 YC051-YD170
2531B	24	Y2 BF 1-7 31-62-25	D03975E K10	SM00518 W YL951-YR328
2531R	24	Y2 BF 0-0 31-62-25	D03975E J10	D45121J A15 YC051-YD170
2531R	24	Y2 BF 0-0 31-62-25	D03975E J10	SM00517 W YL951-YR328
2531Z		BF 0-0 31-62-25	D03975E PERG 1A	D45121J PERG 1F YC051-YD170
2531Z		BF 0-0 31-62-25	D03975E PERG 1A	SM00516 W YL951-YR328
2532B	24	Y2 BG 2-1 31-62-25	D03975E D07	D45141J B17 YC051-YN260
2532R	24	Y2 BG 0-0 31-62-25	D03975E C07	D45141J A17 YC051-YN260

WIRE LIST

D280A108

91-21-11

Section W0310

Page 26

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0313		286A0313				E3-1 ELECTRONIC SHELF - RIGHT (continued)									
2532Z				BG	0-0	31-62-25	D03975E	PERG	1A		D45141J	PERG	1F		YC051-YN260
2534B		24	Y2	CD	3-3	34-61-14	D40149J	A04			TB3102Y	B027	1A		YL951-YR328
2534R		24	Y2	CD	0-0	34-61-14	D40149J	A03			TB3102Y	A027	1A		YL951-YR328
2534Z				CD	0-0	34-61-14	D40149J	PERG	1F		GB03102	ST..	1A		YL951-YR328
2541B		24	Y2	BQ	2-0	73-24-21	D40732J	A04			TB3102Y	B077	1A		YC051-YD157
2541B		24	Y2	BQ	2-2	73-24-21	D40732J	A04			TB3102Y	B077	1A		YD158-YR328
2541R		24	Y2	BQ	0-0	73-24-21	D40732J	B04			TB3102Y	A077	1A		ALL
2541Z				BQ	0-0	73-24-21	D40732J	PERG	1F		GB03102	ST..	1A		ALL
2542B		24	Y2	BR	2-6	73-24-21	D40394J	A05			TB3102Y	B075	1A		ALL
2542R		24	Y2	BR	0-0	73-24-21	D40394J	A06			TB3102Y	A075	1A		ALL
2542Z				BR	0-0	73-24-21	D40394J	PERG	1F		GB03102	ST..	1A		ALL
2543B		24	Y2	BS	2-3	73-24-21	TB3102Y	B077	1A		D03975D	B05			ALL
2543R		24	Y2	BS	0-0	73-24-21	TB3102Y	A077	1A		D03975D	A05			ALL
2543Z				BS	0-0	73-24-21	GB03102	ST..	1A		D03975D	PERG	1A		ALL
2544B		24	Y2	BT	2-4	73-24-21	TB3102Y	B075	1A		D03975E	B05			ALL
2544R		24	Y2	BT	0-0	73-24-21	TB3102Y	A075	1A		D03975E	A05			ALL
2544Z				BT	0-0	73-24-21	GB03102	ST..	1A		D03975E	PERG	1A		ALL
2545B		24	Y2	BU	3-0	73-24-21	TB3102Y	B077	1A		D03973D	B05			ALL
2545R		24	Y2	BU	0-0	73-24-21	TB3102Y	A077	1A		D03973D	A05			ALL
2545Z				BU	0-0	73-24-21	GB03102	ST..	1A		D03973D	PERG	1A		ALL
2546B		24	Y2	BV	2-7	73-24-21	TB3102Y	B075	1A		D03973E	B05			ALL
2546R		24	Y2	BV	0-0	73-24-21	TB3102Y	A075	1A		D03973E	A05			ALL
2546Z				BV	0-0	73-24-21	GB03102	ST..	1A		D03973E	PERG	1A		ALL
2547B		24	Y2	BW	2-3	73-24-21	TB3102Y	B077	1A		D45121J	B07			ALL
2547R		24	Y2	BW	0-0	73-24-21	TB3102Y	A077	1A		D45121J	A07			ALL
2547Z				BW	0-0	73-24-21	GB03102	ST..	1A		D45121J	PERG	1F		ALL
2548B		24	Y2	BX	2-1	73-24-21	TB3102Y	B075	1A		D43157J	A02			ALL
2548R		24	Y2	BX	0-0	73-24-21	TB3102Y	A075	1A		D43157J	A01			ALL
2548Z				BX	0-0	73-24-21	GB03102	ST..	1A		D43157J	PERG	1F		ALL
2549B		24	Y2	BY	2-5	73-24-12	D03975A	K03			TB3102Y	B073	1A		ALL
2549R		24	Y2	BY	0-0	73-24-12	D03975A	J03			TB3102Y	A073	1A		ALL
2549Z				BY	0-0	73-24-12	D03975A	PERG	1A		GB03102	ST..	1A		ALL
2550B		24	Y2	BZ	2-10	73-24-12	TB3102Y	B039	1A		D40732J	A03			YC051-YD157
2550B		24	Y2	BZ	3-0	73-24-12	TB3102Y	B039	1A		D40732J	A03			YD158-YR328
2550R		24	Y2	BZ	0-0	73-24-12	TB3102Y	A039	1A		D40732J	B03			ALL
2550Z				BZ	0-0	73-24-12	GB03102	ST..	1A		D40732J	PERG	1F		ALL
2551B		24	Y2	CA	2-6	73-24-12	TB3102Y	B073	1A		D40394J	B19			ALL
2551R		24	Y2	CA	0-0	73-24-12	TB3102Y	A073	1A		D40394J	A19			ALL
2551Z				CA	0-0	73-24-12	GB03102	ST..	1A		D40394J	PERG	1F		ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 27

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0313	286A0313				E3-1 ELECTRONIC SHELF - RIGHT (continued)										
2552B	24	Y2	CC		3-0	34-61-14	D43147J	B06			TB3102Y	B027	1A		YL951-YR328
2552R	24	Y2	CC		0-0	34-61-14	D43147J	B05			TB3102Y	A027	1A		YL951-YR328
2552Z			CC		0-0	34-61-14	D43147J	PERG	1F		GB03102	ST..	1A		YL951-YR328
2559B	22	X2	CI		3-0	28-41-11	TB3102Y	B043	1A		D40394J	A11			ALL
2559R	22	X2	CI		0-0	28-41-11	TB3102Y	A043	1A		D40394J	A12			ALL
2559Z			CI		0-0	28-41-11	GB03102	ST..	1A		D40394J	PERG	1F		ALL
2563B	24	Y2	CM		2-0	34-61-14	D43147J	B06			D03975B	D02			YC051-YD170
2563B	24	Y2	CM		3-3	34-61-14	TB3102Y	B027	1A		D03975B	D02			YL951-YR328
2563R	24	Y2	CM		0-0	34-61-14	D43147J	B05			D03975B	C02			YC051-YD170
2563R	24	Y2	CM		0-0	34-61-14	TB3102Y	A027	1A		D03975B	C02			YL951-YR328
2563Z			CM		0-0	34-61-14	D43147J	PERG	1F		D03975B	PERG	1A		YC051-YD170
2563Z			CM		0-0	34-61-14	GB03102	ST..	1A		D03975B	PERG	1A		YL951-YR328
2565B	24	Y2	CP		2-4	77-12-11	D40732J	A09			TB3102Y	B069	1A		YC051-YD157
2565B	24	Y2	CP		2-6	77-12-11	D40732J	A09			TB3102Y	B069	1A		YD158-YR328
2565R	24	Y2	CP		0-0	77-12-11	D40732J	B09			TB3102Y	A069	1A		ALL
2565Z			CP		0-0	77-12-11	D40732J	PERG	1F		GB03102	ST..	1A		ALL
2566B	24	Y2	CQ		2-8	77-12-11	TB3102Y	B069	1A		D03973D	B10			ALL
2566R	24	Y2	CQ		0-0	77-12-11	TB3102Y	A069	1A		D03973D	A10			ALL
2566Z			CQ		0-0	77-12-11	GB03102	ST..	1A		D03973D	PERG	1A		ALL
2567B	24	Y2	CR		2-5	77-12-11	TB3102Y	B069	1A		D03975D	B10			ALL
2567R	24	Y2	CR		0-0	77-12-11	TB3102Y	A069	1A		D03975D	A10			ALL
2567Z			CR		0-0	77-12-11	GB03102	ST..	1A		D03975D	PERG	1A		ALL
2568B	24	Y2	CS		2-7	77-31-21	TB3102Y	B069	1A		D45121J	B06			ALL
2568R	24	Y2	CS		0-0	77-31-21	TB3102Y	A069	1A		D45121J	A06			ALL
2568Z			CS		0-0	77-31-21	GB03102	ST..	1A		D45121J	PERG	1F		ALL
2569B	24	Y2	CT		2-6	77-12-21	D40394J	A07			TB3102Y	B071	1A		ALL
2569R	24	Y2	CT		0-0	77-12-21	D40394J	A08			TB3102Y	A071	1A		ALL
2569Z			CT		0-0	77-12-21	D40394J	PERG	1F		GB03102	ST..	1A		ALL
2570B	24	Y2	CU		2-7	77-12-21	TB3102Y	B071	1A		D03973E	B10			ALL
2570R	24	Y2	CU		0-0	77-12-21	TB3102Y	A071	1A		D03973E	A10			ALL
2570Z			CU		0-0	77-12-21	GB03102	ST..	1A		D03973E	PERG	1A		ALL
2571B	24	Y2	CV		2-4	77-12-21	TB3102Y	B071	1A		D03975E	B10			ALL
2571R	24	Y2	CV		0-0	77-12-21	TB3102Y	A071	1A		D03975E	A10			ALL
2571Z			CV		0-0	77-12-21	GB03102	ST..	1A		D03975E	PERG	1A		ALL
2572B	24	Y2	CW		2-7	77-31-21	TB3102Y	B071	1A		D45121J	B05			ALL
2572R	24	Y2	CW		0-0	77-31-21	TB3102Y	A071	1A		D45121J	A05			ALL
2572Z			CW		0-0	77-31-21	GB03102	ST..	1A		D45121J	PERG	1F		ALL
2573B	22	PB	CX		1-10	78-36-21	D40732J	A01			D45121J	B17			YC051-YD157
2573B	22	PB	CX		1-11	78-36-21	D40732J	A01			D45121J	B17			YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0310

Page 28

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0313		286A0313			E3-1 ELECTRONIC SHELF - RIGHT (continued)											
2573R		22		PB	CX	0-0	78-36-21	D40732J	B01			D45121J	A17			ALL
2574B		22		PB	CY	1-10	78-36-21	D40732J	A02			D45121J	B18			YC051-YD157
2574B		22		PB	CY	1-11	78-36-21	D40732J	A02			D45121J	B18			YD158-YR328
2574R		22		PB	CY	0-0	78-36-21	D40732J	B02			D45121J	A18			ALL
2576B		24		Y2	DA	2-11	34-33-21	D45121J	B19			D03973D	H15			ALL
2576R		24		Y2	DA	0-0	34-33-21	D45121J	A19			D03973D	G15			ALL
2576Z					DA	0-0	34-33-21	D45121J	PERG	1F		D03973D	PERG	1A		ALL
2577B		24		Y2	DB	2-3	34-33-21	D45121J	B09			D03975D	H15			ALL
2577R		24		Y2	DB	0-0	34-33-21	D45121J	A09			D03975D	G15			ALL
2577Z					DB	0-0	34-33-21	D45121J	PERG	1F		D03975D	PERG	1A		ALL
2581B		22		X2	DF	2-3	34-57-21	D03653B	B14			TB3101Y	B089	1A		ALL
2581R		22		X2	DF	0-0	34-57-21	D03653B	B13			TB3101Y	A089	1A		ALL
2581Z					DF	0-0	34-57-21	D03653B	PERG	1A		GB03101	ST..	1A		ALL
2582B		24		Y2	DG	2-11	34-57-21	TB3101Y	B089	1A		D03973D	D03			ALL
2582R		24		Y2	DG	0-0	34-57-21	TB3101Y	A089	1A		D03973D	C03			ALL
2582Z					DG	0-0	34-57-21	GB03101	ST..	1A		D03973D	PERG	1A		ALL
2583B		24		Y2	DH	2-3	34-57-21	TB3101Y	B089	1A		D03975D	D03			ALL
2583R		24		Y2	DH	0-0	34-57-21	TB3101Y	A089	1A		D03975D	C03			ALL
2583Z					DH	0-0	34-57-21	GB03101	ST..	1A		D03975D	PERG	1A		ALL
2589B		24		Y2	DN	2-10	22-11-51	D45141J	B13			D03973D	D12			ALL
2589R		24		Y2	DN	0-0	22-11-51	D45141J	A13			D03973D	C12			ALL
2589Z					DN	0-0	22-11-51	D45141J	PERG	1F		D03973D	PERG	1A		ALL
2590B		24		Y2	DP	2-2	22-11-51	D45141J	B12			D03975D	D12			ALL
2590R		24		Y2	DP	0-0	22-11-51	D45141J	A12			D03975D	C12			ALL
2590Z					DP	0-0	22-11-51	D45141J	PERG	1F		D03975D	PERG	1A		ALL
2591B		24		Y2	DQ	2-10	27-32-22	D45141J	B06			D03973D	H01			ALL
2591R		24		Y2	DQ	0-0	27-32-22	D45141J	A06			D03973D	G01			ALL
2591Z					DQ	0-0	27-32-22	D45141J	PERG	1F		D03973D	PERG	1A		ALL
2592B		24		Y2	DR	2-2	27-32-22	D45141J	B16			D03975D	H01			ALL
2592R		24		Y2	DR	0-0	27-32-22	D45141J	A16			D03975D	G01			ALL
2592Z					DR	0-0	27-32-22	D45141J	PERG	1F		D03975D	PERG	1A		ALL
2593B		24		Y2	DS	2-1	34-55-21	D45121J	B16			TB3101Y	B085	1A		ALL
2593R		24		Y2	DS	0-0	34-55-21	D45121J	A16			TB3101Y	A085	1A		ALL
2593Z					DS	0-0	34-55-21	D45121J	PERG	1F		GB03101	ST..	1A		ALL
2594B		24		Y2	DT	2-10	34-55-21	TB3101Y	B085	1A		D03973E	D09			ALL
2594R		24		Y2	DT	0-0	34-55-21	TB3101Y	A085	1A		D03973E	C09			ALL
2594Z					DT	0-0	34-55-21	GB03101	ST..	1A		D03973E	PERG	1A		ALL
2595B		24		Y2	DU	2-2	34-55-21	TB3101Y	B085	1A		D03975E	D09			ALL
2595R		24		Y2	DU	0-0	34-55-21	TB3101Y	A085	1A		D03975E	C09			ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 29

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice Effectivity
W0313	286A0313	E3-1 ELECTRONIC SHELF - RIGHT (continued)		
2595Z		DU 0-0 34-55-21	GB03101 ST.. 1A	D03975E PERG 1A ALL
2596B	24 Y2	DV 2-1 34-31-21	D45141J B05	TB3101Z B081 1A ALL
2596R	24 Y2	DV 0-0 34-31-21	D45141J A05	TB3101Z A081 1A ALL
2596Z		DV 0-0 34-31-21	D45141J PERG 1F	GB03101 ST.. 1A ALL
2597B	24 Y2	DW 2-11 34-31-21	TB3101Z B081 1A	D03973D D15 ALL
2597R	24 Y2	DW 0-0 34-31-21	TB3101Z A081 1A	D03973D C15 ALL
2597Z		DW 0-0 34-31-21	GB03101 ST.. 1A	D03973D PERG 1A ALL
2598B	24 Y2	DX 2-11 34-31-21	TB3101Z B081 1A	D03973B H03 ALL
2598R	24 Y2	DX 0-0 34-31-21	TB3101Z A081 1A	D03973B G03 ALL
2598Z		DX 0-0 34-31-21	GB03101 ST.. 1A	D03973B PERG 1A ALL
2599B	24 Y2	DY 2-2 34-31-21	TB3101Z B081 1A	D03975D D15 ALL
2599R	24 Y2	DY 0-0 34-31-21	TB3101Z A081 1A	D03975D C15 ALL
2599Z		DY 0-0 34-31-21	GB03101 ST.. 1A	D03975D PERG 1A ALL
2600B	24 Y2	DZ 2-1 34-31-21	TB3101Z B081 1A	D03975B H03 ALL
2600R	24 Y2	DZ 0-0 34-31-21	TB3101Z A081 1A	D03975B G03 ALL
2600Z		DZ 0-0 34-31-21	GB03101 ST.. 1A	D03975B PERG 1A ALL
2601B	24 Y2	EA 2-9 34-51-21	D45141J B07	D03973E D03 ALL
2601R	24 Y2	EA 0-0 34-51-21	D45141J A07	D03973E C03 ALL
2601Z		EA 0-0 34-51-21	D45141J PERG 1F	D03973E PERG 1A ALL
2602B	24 Y2	EB 2-1 34-51-21	D45141J B08	D03975E D03 ALL
2602R	24 Y2	EB 0-0 34-51-21	D45141J A08	D03975E C03 ALL
2602Z		EB 0-0 34-51-21	D45141J PERG 1F	D03975E PERG 1A ALL
2603B	22 X2	EC 2-0 34-61-15	D43157J A17	TB3101Y B075 1A ALL
2603R	22 X2	EC 0-0 34-61-15	D43157J A16	TB3101Y A075 1A ALL
2603Z		EC 0-0 34-61-15	D43157J PERG 1F	GB03101 ST.. 1A ALL
2604B	22 X2	ED 2-7 34-61-15	TB3101Y B075 1A	D03973B F01 ALL
2604R	22 X2	ED 0-0 34-61-15	TB3101Y A075 1A	D03973B E01 ALL
2604Z		ED 0-0 34-61-15	GB03101 ST.. 1A	D03973B PERG 1A ALL
2605B	22 X2	EE 2-3 34-61-15	TB3101Y B075 1A	D03975B F01 ALL
2605R	22 X2	EE 0-0 34-61-15	TB3101Y A075 1A	D03975B E01 ALL
2605Z		EE 0-0 34-61-15	GB03101 ST.. 1A	D03975B PERG 1A ALL
2606B	22 X2	EF 2-2 34-61-15	D43157J A19	TB3101Y B077 1A ALL
2606R	22 X2	EF 0-0 34-61-15	D43157J A18	TB3101Y A077 1A ALL
2606Z		EF 0-0 34-61-15	D43157J PERG 1F	GB03101 ST.. 1A ALL
2607B	22 X2	EG 2-11 34-61-15	TB3101Y B077 1A	D03973D D09 ALL
2607R	22 X2	EG 0-0 34-61-15	TB3101Y A077 1A	D03973D C09 ALL
2607Z		EG 0-0 34-61-15	GB03101 ST.. 1A	D03973D PERG 1A ALL
2608B	22 X2	EH 2-2 34-61-15	TB3101Y B077 1A	D03975D D09 ALL
2608R	22 X2	EH 0-0 34-61-15	TB3101Y A077 1A	D03975D C09 ALL

WIRE LIST

D280A108

91-21-11
Section W0310
Page 30
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0313		286A0313			E3-1 ELECTRONIC SHELF - RIGHT (continued)											
2608Z					EH	0-0	34-61-15	GB03101	ST..	1A		D03975D	PERG	1A		ALL
2613B	24	Y2			EM	2-6	22-31-52	D43157J	A04			D03973A	F01			ALL
2613R	24	Y2			EM	0-0	22-31-52	D43157J	A03			D03973A	E01			ALL
2613Z					EM	0-0	22-31-52	D43157J	PERG	1F		D03973A	PERG	1A		ALL
2614B	24	Y2			EN	2-0	22-31-52	D43157J	A07			D03975A	F01			ALL
2614R	24	Y2			EN	0-0	22-31-52	D43157J	A06			D03975A	E01			ALL
2614Z					EN	0-0	22-31-52	D43157J	PERG	1F		D03975A	PERG	1A		ALL
2615B	24	Y2			EP	2-5	34-21-23	D43157J	A13			D03973D	D02			YC051-YC052
2615B	24	Y2			EP	1-8	34-21-23	SM00520		W		D03973D	D02			YC053-YR328
2615R	24	Y2			EP	0-0	34-21-23	D43157J	A12			D03973D	C02			YC051-YC052
2615R	24	Y2			EP	0-0	34-21-23	SM00519		W		D03973D	C02			YC053-YR328
2615Z					EP	0-0	34-21-23	D43157J	PERG	1F		D03973D	PERG	1A		YC051-YC052
2615Z					EP	0-0	34-21-23	SM00521		W		D03973D	PERG	1A		YC053-YR328
2616B	24	Y2			EQ	2-0	34-21-23	D43157J	A15			D03975D	D02			ALL
2616R	24	Y2			EQ	0-0	34-21-23	D43157J	A14			D03975D	C02			ALL
2616Z					EQ	0-0	34-21-23	D43157J	PERG	1F		D03975D	PERG	1A		ALL
2617B	24	Y2			ER	2-1	34-21-24	D43147J	B04			TB3101Y	B073	1A		ALL
2617R	24	Y2			ER	0-0	34-21-24	D43147J	B03			TB3101Y	A073	1A		ALL
2617Z					ER	0-0	34-21-24	D43147J	PERG	1F		GB03101	ST..	1A		ALL
2618B	24	Y2			ES	2-3	34-21-24	TB3101Y	B073	1A		D03975E	D05			ALL
2618R	24	Y2			ES	0-0	34-21-24	TB3101Y	A073	1A		D03975E	C05			ALL
2618Z					ES	0-0	34-21-24	GB03101	ST..	1A		D03975E	PERG	1A		ALL
2619B	24	Y2			ET	2-4	34-21-24	TB3101Y	B073	1A		D03975A	K15			ALL
2619R	24	Y2			ET	0-0	34-21-24	TB3101Y	A073	1A		D03975A	J15			ALL
2619Z					ET	0-0	34-21-24	GB03101	ST..	1A		D03975A	PERG	1A		ALL
2620B	24	Y2			EU	2-1	34-21-24	D43147J	B02			TB3101Y	B071	1A		ALL
2620R	24	Y2			EU	0-0	34-21-24	D43147J	B01			TB3101Y	A071	1A		ALL
2620Z					EU	0-0	34-21-24	D43147J	PERG	1F		GB03101	ST..	1A		ALL
2621B	24	Y2			EV	2-5	34-21-24	TB3101Y	B071	1A		D03973E	D05			ALL
2621R	24	Y2			EV	0-0	34-21-24	TB3101Y	A071	1A		D03973E	C05			ALL
2621Z					EV	0-0	34-21-24	GB03101	ST..	1A		D03973E	PERG	1A		ALL
2622B	24	Y2			EW	2-8	34-21-24	TB3101Y	B071	1A		D03973A	K15			ALL
2622R	24	Y2			EW	0-0	34-21-24	TB3101Y	A071	1A		D03973A	J15			ALL
2622Z					EW	0-0	34-21-24	GB03101	ST..	1A		D03973A	PERG	1A		ALL
2623B	24	Y2			EX	2-7	79-31-11	TB3102Z	B061	1A		D03973D	F14			ALL
2623R	24	Y2			EX	0-0	79-31-11	TB3102Z	A061	1A		D03973D	E14			ALL
2623Z					EX	0-0	79-31-11	GB03102	ST..	1A		D03973D	PERG	1A		ALL
2624B	24	Y2			EY	2-6	79-31-11	TB3102Z	B061	1A		D03973E	B06			ALL
2624R	24	Y2			EY	0-0	79-31-11	TB3102Z	A061	1A		D03973E	A06			ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 31

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From				To						
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0313	286A0313			E3-1 ELECTRONIC SHELF - RIGHT (continued)											
2624Z				EY	0-0	79-31-11	GB03102	ST..	1A		D03973E	PERG	1A		ALL
2625B	24		Y2	EZ	2-6	79-31-11	TB3102Z	B061	1A		D03975D	F14			ALL
2625R	24		Y2	EZ	0-0	79-31-11	TB3102Z	A061	1A		D03975D	E14			ALL
2625Z				EZ	0-0	79-31-11	GB03102	ST..	1A		D03975D	PERG	1A		ALL
2626B	24		Y2	FA	2-5	79-31-11	TB3102Z	B061	1A		D03975E	B06			ALL
2626R	24		Y2	FA	0-0	79-31-11	TB3102Z	A061	1A		D03975E	A06			ALL
2626Z				FA	0-0	79-31-11	GB03102	ST..	1A		D03975E	PERG	1A		ALL
2628B	24		Y2	FC	2-7	34-57-21	D42007J	A03			D03653B	B08			ALL
2628R	24		Y2	FC	0-0	34-57-21	D42007J	A02			D03653B	B07			ALL
2628Z				FC	0-0	34-57-21	D42007J	PERG	1F		D03653B	PERG	1A		ALL
2629B	24		Y2	FD	2-3	34-57-21	D03653B	B11			D45121J	B20			ALL
2629R	24		Y2	FD	0-0	34-57-21	D03653B	B10			D45121J	A20			ALL
2629Z				FD	0-0	34-57-21	D03653B	PERG	1A		D45121J	PERG	1F		ALL
2630B	24		M5	FE	2-1	34-57-21	D03653B	B02			D04277J	B01			ALL
2630R	24		M5	FE	0-0	34-57-21	D03653B	B01			D04277J	A01			ALL
2630ZI				FE	0-0	34-57-21	D03653B	DED			D04277J	B02			ALL
2630ZO				FE	0-0	34-57-21	D03653B	PERG	1A		D04277J	PERG	1F		ALL
2631B	24		Y2	FF	2-1	34-57-21	D42165J	A02			D03653B	D02			ALL
2631R	24		Y2	FF	0-0	34-57-21	D42165J	A01			D03653B	D01			ALL
2631Z				FF	0-0	34-57-21	D42165J	PERG	1F		D03653B	PERG	1A		ALL
2632B	24		Y2	FG	2-1	34-57-21	D42165J	A04			D03653B	D08			ALL
2632R	24		Y2	FG	0-0	34-57-21	D42165J	A03			D03653B	D07			ALL
2632Z				FG	0-0	34-57-21	D42165J	PERG	1F		D03653B	PERG	1A		ALL
2633B	24		Y2	FH	2-1	34-57-21	D42165J	A06			D03653B	D15			ALL
2633R	24		Y2	FH	0-0	34-57-21	D42165J	A05			D03653B	D14			ALL
2633Z				FH	0-0	34-57-21	D42165J	PERG	1F		D03653B	PERG	1A		ALL
2634B	22		X2	FI	2-1	34-57-21	D03653B	C11			D42165J	A08			ALL
2634R	22		X2	FI	0-0	34-57-21	D03653B	C10			D42165J	A07			ALL
2634Z				FI	0-0	34-57-21	D03653B	PERG	1A		D42165J	PERG	1F		ALL
2636B	24		Y2	FK	2-1	34-45-11	D43147J	A04			TB3101Y	B069	1A		ALL
2636R	24		Y2	FK	0-0	34-45-11	D43147J	A03			TB3101Y	A069	1A		ALL
2636Z				FK	0-0	34-45-11	D43147J	PERG	1F		GB03101	ST..	1A		ALL
2637B	24		Y2	FM	2-7	34-45-11	TB3101Y	B069	1A		D03973D	F01			ALL
2637R	24		Y2	FM	0-0	34-45-11	TB3101Y	A069	1A		D03973D	E01			ALL
2637Z				FM	0-0	34-45-11	GB03101	ST..	1A		D03973D	PERG	1A		ALL
2638B	24		Y2	FL	2-4	34-45-11	TB3101Y	B069	1A		D03975D	F01			ALL
2638R	24		Y2	FL	0-0	34-45-11	TB3101Y	A069	1A		D03975D	E01			ALL
2638Z				FL	0-0	34-45-11	GB03101	ST..	1A		D03975D	PERG	1A		ALL
2639B	24		Y2	FN	2-2	34-49-11	D43147J	A11			TB3101Y	B067	1A		ALL

WIRE LIST

D280A108

91-21-11
Section W0310
Page 32
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0313		286A0313			E3-1 ELECTRONIC SHELF - RIGHT (continued)											
2639R		24		Y2	FN	0-0	34-49-11	D43147J	A10			TB3101Y	A067	1A		ALL
2639Z					FN	0-0	34-49-11	D43147J	PERG	1F		GB03101	ST..	1A		ALL
2640B		24		Y2	FP	2-6	34-49-11	TB3101Y	B067	1A		D03973D	B09			ALL
2640R		24		Y2	FP	0-0	34-49-11	TB3101Y	A067	1A		D03973D	A09			ALL
2640Z					FP	0-0	34-49-11	GB03101	ST..	1A		D03973D	PERG	1A		ALL
2641B		24		Y2	FQ	2-5	34-49-11	TB3101Y	B067	1A		D03975D	B09			ALL
2641R		24		Y2	FQ	0-0	34-49-11	TB3101Y	A067	1A		D03975D	A09			ALL
2641Z					FQ	0-0	34-49-11	GB03101	ST..	1A		D03975D	PERG	1A		ALL
2642B		24		Y2	FR	2-1	34-41-11	D45141J	B14			D04297J	B06			YC051-YC052
2642B		24		Y2	FR	1-10	34-41-11	D45141J	B14			D40149J	B10			YC053-YR328
2642R		24		Y2	FR	0-0	34-41-11	D45141J	A14			D04297J	B05			YC051-YC052
2642R		24		Y2	FR	0-0	34-41-11	D45141J	A14			D40149J	B09			YC053-YR328
2642Z					FR	0-0	34-41-11	D45141J	PERG	1F		D04297J	PERG	1F		YC051-YC052
2642Z					FR	0-0	34-41-11	D45141J	PERG	1F		D40149J	PERG	1F		YC053-YR328
2643B		24		7K	FS	2-9	34-41-11	D04297J	A12			TB3101Z	B057	1A		YC051-YC052
2643B		24		7K	FS	2-6	34-41-11	D40149J	B14			TB3101Z	B057	1A		YC053-YR328
2643W		24		7K	FS	0-0	34-41-11	D04297J	A11			TB3101Z	A057	1A		YC051-YC052
2643W		24		7K	FS	0-0	34-41-11	D40149J	B13			TB3101Z	A057	1A		YC053-YR328
2643Z					FS	0-0	34-41-11	D04297J	PERG	1F		GB03101	ST..	1A		YC051-YC052
2643Z					FS	0-0	34-41-11	D40149J	PERG	1F		GB03101	ST..	1A		YC053-YR328
2644B		24		7K	FT	2-4	34-41-11	TB3101Z	B053	1A		D03975F	K01			ALL
2644W		24		7K	FT	0-0	34-41-11	TB3101Z	A053	1A		D03975F	J01			ALL
2644Z					FT	0-0	34-41-11	GB03101	ST..	1A		D03975F	DED			ALL
2645B		24		7K	FU	2-3	34-41-11	TB3101Z	B057	1A		D03975F	B01			ALL
2645W		24		7K	FU	0-0	34-41-11	TB3101Z	A057	1A		D03975F	A01			ALL
2645Z					FU	0-0	34-41-11	GB03101	ST..	1A		D03975F	DED			ALL
2647B		22		VX	FW	1-8	77-31-21	D40394J	B11			D40732J	A07			YC051-YD157
2647B		22		VX	FW	1-10	77-31-21	D40394J	B11			D40732J	A07			YD158-YR328
2647W		22		VX	FW	0-0	77-31-21	D40394J	B12			D40732J	B07			ALL
2647Z					FW	0-0	77-31-21	D40394J	B13			D40732J	A08			ALL
2648B		24		Y2	FX	2-10	22-11-51	D45141J	B11			TB3101Y	B051	1A		ALL
2648R		24		Y2	FX	0-0	22-11-51	D45141J	A11			TB3101Y	A051	1A		ALL
2648Z					FX	0-0	22-11-51	D45141J	PERG	1F		GB03101	ST..	1A		ALL
2649B		24		Y2	FY	2-1	22-11-51	TB3101Y	B051	1A		D03973E	F05			ALL
2649R		24		Y2	FY	0-0	22-11-51	TB3101Y	A051	1A		D03973E	E05			ALL
2649Z					FY	0-0	22-11-51	GB03101	ST..	1A		D03973E	PERG	1A		ALL
2650B		24		Y2	FZ	2-8	22-11-51	TB3101Y	B051	1A		D03975E	F05			ALL
2650R		24		Y2	FZ	0-0	22-11-51	TB3101Y	A051	1A		D03975E	E05			ALL
2650Z					FZ	0-0	22-11-51	GB03101	ST..	1A		D03975E	PERG	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 33

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number		Description			From	To							
Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0313	286A0313		E3-1 ELECTRONIC SHELF - RIGHT (continued)											
2657B	24	Y2	GG	2-10	27-81-41	TB3101Y	B033	1A		D03975E	F01			ALL
2657R	24	Y2	GG	0-0	27-81-41	TB3101Y	A033	1A		D03975E	E01			ALL
2657Z			GG	0-0	27-81-41	GB03101	ST..	1A		D03975E	PERG	1A		ALL
2663B	24	Y2	GM	1-9	31-62-25	SM00515		W		D45141J	B03			YL951-YR328
2663R	24	Y2	GM	0-0	31-62-25	SM00514		W		D45141J	A03			YL951-YR328
2663Z			GM	0-0	31-62-25	SM00513		W		D45141J	PERG	1F		YL951-YR328
2664B	24	Y2	GN	1-9	31-62-25	SM00518		W		D45141J	B04			YL951-YR328
2664R	24	Y2	GN	0-0	31-62-25	SM00517		W		D45141J	A04			YL951-YR328
2664Z			GN	0-0	31-62-25	SM00516		W		D45141J	PERG	1F		YL951-YR328
2665B	24	Y2	GP	1-10	31-62-25	SM00515		W		D45121J	B14			YL951-YR328
2665R	24	Y2	GP	0-0	31-62-25	SM00514		W		D45121J	A14			YL951-YR328
2665Z			GP	0-0	31-62-25	SM00513		W		D45121J	PERG	1F		YL951-YR328
2666B	24	Y2	GQ	1-10	31-62-25	SM00518		W		D45121J	B15			YL951-YR328
2666R	24	Y2	GQ	0-0	31-62-25	SM00517		W		D45121J	A15			YL951-YR328
2666Z			GQ	0-0	31-62-25	SM00516		W		D45121J	PERG	1F		YL951-YR328
2669B	24	Y2	GT	3-1	31-62-15	D40149J	B02			SP00159		W		YC053-YR328
2669R	24	Y2	GT	0-0	31-62-15	D40149J	B01			SP00157		W		YC053-YR328
2669Z			GT	0-0	31-62-15	D40149J	PERG	1F		SP00161		W		YC053-YR328
2670B	24	Y2	GU	1-11	31-62-25	D40149J	A10			TB3101Y	B091	1A		YC053-YR328
2670R	24	Y2	GU	0-0	31-62-25	D40149J	A09			TB3101Y	A091	1A		YC053-YR328
2670Z			GU	0-0	31-62-25	D40149J	PERG	1F		GB03101	ST..	1A		YC053-YR328
2671B	24	7K	GV	2-6	34-41-11	D40149J	A12			TB3101Z	B053	1A		YC053-YR328
2671W	24	7K	GV	0-0	34-41-11	D40149J	A11			TB3101Z	A053	1A		YC053-YR328
2671Z			GV	0-0	34-41-11	D40149J	PERG	1F		GB03101	ST..	1A		YC053-YR328
2672B	24	Y2	GW	3-3	34-41-11	D40149J	A02			TB3101Z	B017	1A		YC053-YR328
2672R	24	Y2	GW	0-0	34-41-11	D40149J	A01			TB3101Z	A017	1A		YC053-YR328
2672Z			GW	0-0	34-41-11	D40149J	PERG	1F		GB03101	ST..	1A		YC053-YR328
2673B	24	Y2	GX	2-1	34-21-14	D40149J	B06			D43147J	B08			YC053-YR328
2673R	24	Y2	GX	0-0	34-21-14	D40149J	B05			D43147J	B07			YC053-YR328
2673Z			GX	0-0	34-21-14	D40149J	PERG	1F		D43147J	PERG	1F		YC053-YR328
2674B	24	Y2	GY	1-3	34-21-23	SM00520		W		D43157J	A13			YC053-YR328
2674R	24	Y2	GY	0-0	34-21-23	SM00519		W		D43157J	A12			YC053-YR328
2674Z			GY	0-0	34-21-23	SM00521		W		D43157J	PERG	1F		YC053-YR328
2675B	24	Y2	GZ	1-7	34-21-23	SM00520		W		D40149J	B04			YC053-YR328
2675R	24	Y2	GZ	0-0	34-21-23	SM00519		W		D40149J	B03			YC053-YR328
2675Z			GZ	0-0	34-21-23	SM00521		W		D40149J	PERG	1F		YC053-YR328
2676B	24	Y2	HA	2-1	34-21-24	D40149J	A06			D43147J	B10			YC053-YR328
2676R	24	Y2	HA	0-0	34-21-24	D40149J	A05			D43147J	B09			YC053-YR328
2676Z			HA	0-0	34-21-24	D40149J	PERG	1F		D43147J	PERG	1F		YC053-YR328

WIRE LIST

D280A108

91-21-11

Section W0310

Page 34

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0313		286A0313			E3-1 ELECTRONIC SHELF - RIGHT (continued)											
2677B		24		Y2	HB	3-1	34-21-13	SP00508				D40149J		B12		YC053-YR328
2677R		24		Y2	HB	0-0	34-21-13	SP00507				D40149J		B11		YC053-YR328
2677Z					HB	0-0	34-21-13	SP00509				D40149J		PERG	1F	YC053-YR328
3501B		24		Y3	XA	2-5	79-31-11	D40732J		A13		TB3102Z		B061	1A	YC051-YD157
3501B		24		Y3	XA	2-7	79-31-11	D40732J		A13		TB3102Z		B061	1A	YD158-YR328
3501R		24		Y3	XA	0-0	79-31-11	D40732J		B13		TB3102Z		A061	1A	ALL
3501Y		24		Y3	XA	0-0	79-31-11	D40732J		A14		TB3102Y		B065	1A	ALL
3501Z					XA	0-0	79-31-11	D40732J		PERG	1F	GB03102		ST..	1A	ALL
401CO					ZB	0-0	31-62-22	D03975C		= 12		D40401J		= C1		ALL
401CX				0F	ZB	1-7	31-62-22	D03975C		12	DN	D40401J		= A1		ALL

WIRE LIST

D280A108

91-21-11

Section W0310

Page 35 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321				E3-2 SHELF										
0001	22		PA		3-0	31-31-11	D43219J	A07			D02295C	1			ALL
0002	22		PA		1-6	31-31-11	GD03204	AC..	1A		D02295C	7			ALL
0003	22		PA		1-9	31-31-11	GD03204	DC..	1A		D02295A	J15			ALL
0004	22		PA		1-9	31-31-11	GD03204	DC..	1A		D02295A	K15			ALL
0005	22		PA		1-9	31-31-11	GD03204	DC..	1A		D02295D	J15			ALL
0006	22		PA		1-9	31-31-11	GD03204	DC..	1A		D02295D	K15			ALL
0007	22		PA		2-5	31-31-11	D40486J	B07			D02295A	A11			ALL
0008	22		PA		2-7	31-31-11	D40486J	A07			D43209J	A08			ALL
0009	22		PA		2-8	31-31-11	D40596J	A05			D43209J	A07			ALL
0010	22		PA		2-8	31-31-11	D40596J	A10			D43209J	A06			ALL
0014	22		PA		2-4	23-32-14	D40426J		6		D40468J	A07			YD158-YN260
0014	22		PA		2-4	44-21-22	D40426J		6		D40468J	A07			YN501-YR328
0015	24		PK		1-6	31-35-01	D02295E	H11			SM00003		W		ALL
0016	24		PK		1-6	31-35-01	SM00003		W		D02295E	H12			ALL
0017	24		PK		1-5	31-35-01	D43261J	A03			SM00004		W		ALL
0018	24		PK		1-7	31-35-01	SM00004		W		D02295D	H15			ALL
0019	24		PK		1-7	31-35-01	SM00004		W		D02295D	G15			ALL
001CO				DI	0-0	23-32-21	D02813C	= C2			D02819	= C1			YD158-YD170
001CX			OF	DI	1-0	23-32-21	D02813C	A2	DN		D02819	= A1			YD158-YD170
0020	24		PK		2-3	31-35-01	D43261J	A06			D02295B	H12			ALL
0021	24		PK		1-5	31-35-01	D43261J	A04			SM00003		W		ALL
0022	22		PA		2-4	31-31-14	D41819J		6		TB3201Z	A069	1A		ALL
0023	24		PK		2-4	31-31-14	D02295B	H03			TB3201Z	A069	1A		ALL
0024	22		PA		1-6	31-31-14	TB3201Z	A077	1A		TB3201Z	A069	1A		ALL
0025	22		G5		3-1	27-24-11	D03685B		13		TB3201Z	B069	1A		ALL
0026	22		PA		2-2	31-31-11	D02295A	B11			D43209J	A03			ALL
0027	22		PA		1-9	31-31-14	TB3201Z	A069	1A		TB3201Z	B069	1A		ALL
0028	24		G6		1-9	73-22-11	D40470J	A04			D40392J	B07			ALL
0029	24		G6		1-9	73-22-31	D40470J	B01			D40392J	B08			ALL
002CO				DJ	0-0	23-32-21	D02821	= C1			D43279J	= C1			YD158-YD170
002CX			OF	DJ	1-1	23-32-21	D02821	= A1			D43279J	= A1			YD158-YD170
0030	22		PA		2-0	73-23-11	D40486J	A03			D40392J	B10			ALL
0031	22		PA		1-10	73-23-11	D40468J	A06			D40392J	B11			ALL
0032	24		PK		1-11	31-31-17	D02295D	D01			D40392J	A16			YD158-YD170, YL953-YN501
0032	24		G6		1-11	31-31-17	D02295D	D01			D40392J	A16			YL951-YL952, YR301-YR328
0034	22		PA		3-3	31-31-14	D02295B	C04			D43203J	A01			ALL
0035	22		PA		1-8	31-31-14	D02295B	C05			GD03204	AC..	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0320

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321		286A0321				E3-2 SHELF (continued)										
0036		22		PA		1-11	31-31-14	D43203J	A02			GD03201	AC..	1A		ALL
0037		22		PA		2-4	31-31-14	D02295B	C06			TB3201Z	A065	1A		ALL
0038		22		PA		3-2	31-31-14	D43203J	A03			TB3201Z	A065	1A		ALL
0039		22		PA		2-4	31-31-14	D02295B	C09			TB3201Z	A065	1A		ALL
0040		22		PA		3-2	31-31-14	D43203J	A04			TB3201Z	A065	1A		ALL
0041		22		PA		3-3	31-31-14	D02295B	C07			D43203J	A05			ALL
0042		22		PA		1-8	31-31-14	D02295B	C08			GD03204	AC..	1A		ALL
0043		22		PA		1-11	31-31-14	D43203J	A06			GD03201	AC..	1A		ALL
0044		22		PA		2-0	31-31-14	D02295E	C04			D43205J	A01			ALL
0045		22		PA		1-8	31-31-14	D02295E	C05			GD03204	AC..	1A		ALL
0046		22		PA		1-9	31-31-14	D43205J	A02			GD03203	AC..	1A		ALL
0047		22		PA		2-4	31-31-14	TB3201Z	B065	1A		D02295E	C06			ALL
0048		22		PA		1-11	31-31-14	D43205J	A03			TB3201Z	B065	1A		ALL
0049		22		PA		2-4	31-31-14	D02295E	C09			TB3201Z	B065	1A		ALL
0050		22		PA		1-11	31-31-14	TB3201Z	B065	1A		D43205J	A04			ALL
0051		22		PA		2-0	31-31-14	D02295E	C07			D43205J	A05			ALL
0052		22		PA		1-8	31-31-14	D02295E	C08			GD03204	AC..	1A		ALL
0053		22		PA		1-9	31-31-14	D43205J	A06			GD03203	AC..	1A		ALL
0054		24		PK		2-11	31-31-15	D40462J	A04			D02295A	G03			ALL
0055		24		PK		2-2	31-31-15	D40470J	B05			D02295D	H03			ALL
0056		24		PK		2-10	31-31-15	D40426J	2			D02295A	H03			ALL
0057		24		PK		2-10	31-31-15	D40426J	3			D02295D	F01			ALL
0058		24		PK		2-9	31-31-15	D40426J	1			D02295B	J02			YC051-YN235
0058		24		PK		3-0	31-31-15	TB3201Y	A035	1A		D02295B	J02			YN236-YR328
0059		22		PA		2-11	31-31-15	D40462J	A09			D02295A	E01			ALL
0060		22		PA		2-11	31-31-15	D40462J	A10			D02295D	B05			ALL
0061		22		PA		2-11	31-31-15	D40462J	A11			D02295D	K01			ALL
0062		22		PA		2-10	31-31-15	D40462J	A12			D02295E	J03			ALL
0063		22		PA		2-11	31-31-15	D40462J	A13			D02295A	A05			ALL
0064		22		PA		2-11	31-31-15	D40462J	A14			D02295A	J01			ALL
0065		22		PA		2-11	31-31-15	D40462J	A15			D02295A	D01			ALL
0066		22		G5		1-11	31-31-15	D02295D	G03			D40392J	B15			ALL
0067		22		G5		1-11	31-31-15	D40392J	B16			D02295A	K01			ALL
0068		24		G6		2-0	31-31-15	D02295E	J02			D42361J	A11			ALL
0069		24		G6		2-1	31-31-15	D02295D	A01			D42361J	B07			ALL
0070		22		PA		2-1	34-21-15	D02295D	E01			D42361J	A07			ALL
0071		24		G6		1-10	31-31-15	D02295E	K03			D45147J	A02			ALL
0072		24		B6		1-11	31-31-15	D02295D	E03			D45147J	B02			ALL
0073		22		G5		2-2	34-61-12	D02295B	J04			D42261J	A14			ALL

WIRE LIST

D280A108

91-21-11

Section W0320

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321			E3-2 SHELF (continued)											
0074	24		B6		3-5	31-31-15	D02295E	K02			D40362J	B01			ALL
0075	24		B6		3-4	31-31-15	D02295B	K02			D40940J	A01			ALL
0076	24		B6		3-5	31-31-15	D02295D	F03			D40940J	B01			ALL
0077	24		PK		1-11	31-31-15	D02295B	K01			D43263J	A10			ALL
0078	20		G5		2-0	27-31-11	D40392J	A07			D40194J	B19			ALL
0080	24		G6		2-0	31-31-15	D02295A	F03			D42363J	A02			ALL
0081	24		G6		2-0	31-31-15	D02295D	D03			D42363J	B02			ALL
0082	24		G6		1-7	31-31-15	D02295A	J03			SM00010		W		ALL
0083	22		PA		2-6	26-16-21	D40486J	B05			D40462J	A05			YC067-YD158
0083	22		PA		1-11	26-16-21	SM00048		W		D40462J	A05			YL951-YR328
0084	24		G6		1-7	31-31-15	D02295A	K03			SM00011		W		ALL
0085	24		PK		2-4	31-31-15	D02295E	J01			D40486J	A04			ALL
0086	24		PK		2-6	31-31-15	D02295D	A05			D40596J	A04			ALL
0087	24		G6		1-7	31-31-15	D02295D	J03			SM00009		W		ALL
0088	24		G6		2-6	73-22-31	D40426J	12			D40392J	B09			YC051-YC055, YD158-YR328
0088	24		G6		2-5	73-22-31	D40426J	12			D40392J	B09			YC056-YD157
0089	24		G6		1-7	31-31-15	D02295D	K03			SM00008		W		ALL
0090	22		G5		3-2	27-83-11	D40596J	B02			D03683A	62			ALL
0091	24		PK		2-1	27-18-11	TB3201Z	B073	1A		GD03204	AC..	1A		ALL
0092	24		PK		2-1	31-31-15	D02295B	J03			D40470J	B03			ALL
0093	24		G6		2-1	31-31-17	D02295A	A01			D42361J	B08			YC051-YD170, YL953-YR328
0093	24		PK		2-1	31-31-17	D02295A	A01			D42361J	B08			YL951-YL952
0094	24		PK		1-11	31-31-17	D02295D	B01			D45127J	A02			YC051-YL999, YN501
0094	24		G6		1-11	31-31-17	D02295D	B01			D45127J	A02			YN231-YN260, YR301-YR328
0095	22		G5		2-3	27-32-11	D41839J	8			TB3201Y	A033	1A		YC051-YL952, YN231-YN501
0095	22		G5		1-10	27-32-11	D41839J	8			SM00066		W		YL953-YL999, YR301-YR328
0096	22		G5		2-8	27-32-11	D41839J	9			TB3201Y	A011	1A		ALL
0097	22		G5		2-8	27-32-11	D41839J	10			D03683A	10			ALL
0098	24		G6		3-3	31-31-17	D02295A	B01			D45157J	B06			ALL
0099	24		G6		2-1	31-31-17	D02295A	C01			D42361J	B15			ALL
0101	24		G6		2-6	27-21-11	D40392J	A20			TB3201Y	A041	1A		YC051-YD153
0102	24		G6		2-6	27-21-11	D40392J	B20			TB3201Y	B041	1A		YC051-YD153
0105	24		G6		2-0	27-28-11	D43263J	A18			D40194J	A05			ALL
0106	24		G6		2-0	27-28-11	D43263J	A19			D40194J	A06			ALL

WIRE LIST

D280A108

91-21-11

Section W0320

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321		286A0321			E3-2 SHELF (continued)											
0110		20		G5		2-1	27-53-11	D42361J	A05			D40194J	B10			ALL
0111		20		G5		2-1	27-53-11	D42361J	B12			D40194J	B11			ALL
0112		20		G5		2-1	27-53-11	D42361J	B14			D40194J	A03			ALL
0114		24		PK		1-9	27-62-21	D40468J	B06			SM00015		W		ALL
0117		24		PK		3-3	27-81-31	D03683A	50			D43261J	B03			ALL
0118		24		PK		3-2	27-81-31	D03685A	50			D43261J	A05			ALL
0119		22		G5		2-3	27-83-11	D45117J	B20			D03683A	3			ALL
0120		22		G5		2-11	27-83-21	D40392J	A04			D03685A	5			ALL
0121		22		G5		2-11	27-83-21	D40392J	A02			D03685A	3			ALL
0122		22		PA		2-11	27-83-21	D40392J	A03			D03685A	62			ALL
0125		20		CQ		2-0	29-11-11	D40486J	A09			D43046J	A01			ALL
0126		20		CQ		2-0	29-11-11	D40486J	A10			D43046J	B01			ALL
0127		20		G5		1-11	27-32-11	D43261J	B14			GD03204	AC..	1A		ALL
0128		22		G5		1-8	27-32-11	D03683B	56			GD03201	AC..	1A		ALL
0129		22		G5		0-6	27-32-11	D03683B	2			GD03209	DC..	1F		ALL
0130		22		G5		1-8	27-32-11	D03683A	14			GD03201	DC..	1A		ALL
0131		22		G5		3-10	27-32-11	D40053J	A09			GD03205	AC..	1A		ALL
0132		22		PA		1-6	31-31-14	TB3201Z	A069	1A		TB3201Z	A065	1A		ALL
0133		22		CQ		2-6	27-32-11	D41819J	20			SM00321		W		YC051-YC055, YC059-YN501
0133		22		G5		2-7	27-32-11	D41819J	20			SM00321		W		YC056-YC057
0133		22		CQ		2-7	27-32-11	D41819J	20			SM00321		W		YC058
0133		22		CQ		1-8	27-32-11	D41819J	20			SM00321		W		YR301-YR328
0134		22		PA		2-1	27-32-11	D40462J	A01			D03683A	20			ALL
0136		24		PK		2-1	27-32-11	D40462J	A03			TB3201Y	A013	1A		ALL
0137		24		PK		1-11	27-32-11	TB3201Y	A013	1A		D03683B	19			ALL
0138		24		G6		2-1	27-32-11	D40462J	A16			D03683A	74			ALL
0139		22		PA		1-6	31-31-14	TB3201Z	B069	1A		TB3201Z	B065	1A		ALL
0140		22		G5		2-0	27-32-11	TB3201X	A001	1A		D03683A	84			ALL
0141		22		G5		2-0	27-32-11	TB3201X	A002	1A		D03683B	76			ALL
0142		22		G5		2-0	27-32-11	TB3201X	A003	1A		D03683B	74			ALL
0143		22		G5		2-0	27-32-11	TB3201X	A004	1A		D03683B	78			ALL
0144		22		G5		1-11	27-32-11	TB3201X	A005	1A		D03683B	49			ALL
0145		22		G5		1-11	27-32-11	TB3201Y	A009	1A		D03683B	34			ALL
0146		22		G5		1-11	27-32-11	TB3201X	A007	1A		D03683B	48			YC051-YL999, YR301-YR328
0146		22		G5		1-11	27-32-11	TB3201Y	A009	1A		D03683B	48			YN231-YN501
0147		22		G5		1-11	27-32-11	TB3201Y	A009	1A		D03683A	100			YC051-YL952
0147		22		G5		1-11	27-32-11	TB3201X	A006	1A		D03683A	100			YL953-YR328

WIRE LIST

D280A108

91-21-11

Section W0320

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321				E3-2 SHELF (continued)										
0148	22		G5		1-9	27-32-11	TB3201Y	A009	1A		GD03201	DC..	1A		ALL
0151	22		PA		2-0	23-27-12	D40594J	A07			D45157J	A01			YC051-YD157
0151	22		PA		2-0	23-27-38	D40594J	A07			D45157J	A01			YD158-YL999, YN501-YR328 YN231-YN260
0151	22		G5		2-0	23-27-38	D40594J	A07			D45157J	A01			YC051-YD157
0152	22		PA		2-7	23-27-12	D40470J	A10			D45157J	B01			YD158-YL999, YN501-YR328 YN231-YN260
0152	22		PA		2-7	23-27-38	D40470J	A10			D45157J	B01			YC051-YD157
0152	22		G5		2-7	23-27-38	D40470J	A10			D45157J	B01			YD158-YL999, YN501-YR328 YN231-YN260
0153	22		PA		2-7	23-27-12	D40470J	B10			D45157J	A02			YC051-YD157
0153	22		PA		2-7	23-27-38	D40470J	B10			D45157J	A02			YD158-YL999, YN501-YR328 YN231-YN260
0153	22		G5		2-7	23-27-38	D40470J	B10			D45157J	A02			YC051-YD157
0154	22		PA		2-7	23-27-12	D40470J	B08			D45157J	B02			YD158-YL999, YN501-YR328 YN231-YN260
0154	22		PA		2-7	23-27-38	D40470J	B08			D45157J	B02			YC051-YD157
0154	22		G5		2-7	23-27-38	D40470J	B08			D45157J	B02			YD158-YL999, YN501-YR328 YN231-YN260
0157	22		PA		2-7	23-27-14	D40470J	A09			D45157J	A04			YC051-YD157
0157	22		PA		2-7	23-27-38	D40470J	A09			D45157J	A04			YD158-YL999, YN501-YR328 YN231-YN260
0157	22		G5		2-7	23-27-38	D40470J	A09			D45157J	A04			YC051-YD157
0158	22		PA		2-7	23-27-14	D40470J	B09			D45157J	B04			YD158-YL999, YN501-YR328 YN231-YN260
0158	22		PA		2-7	23-27-38	D40470J	B09			D45157J	B04			YC051-YD157
0158	22		G5		2-7	23-27-38	D40470J	B09			D45157J	B04			YD158-YL999, YN501-YR328 YN231-YN260
0159	20		G5		2-7	SPARE	D40426J	8			D45157J	A05			YC051-YC053
0161	22		PA		2-7	SPARE	D40426J	11			D45157J	A06			YC051-YD170
0165	22		PA		2-11	31-31-11	D43219J	A08			GD03204	DC..	1A		ALL
0166	22		PA		1-5	22-23-11	D45117J	A02			SM00005		W		ALL
0167	22		PA		1-5	22-23-11	D03683A	51			SM00005		W		ALL
0168	22		PA		1-3	22-23-11	D03685A	61			SM00005		W		ALL
0169	22		PA		1-8	22-23-11	D03685A	51			GD03201	DC..	1A		ALL
0170	22		PA		3-6	24-28-11	D02295A	G07			D40362J	B02			ALL
0171	22		PA		3-6	24-28-11	D02295D	H07			D40362J	A02			ALL
0172	24		PK		3-6	24-33-13	D40362J	A06			D02295A	B03			ALL
0173	24		PK		3-6	24-33-13	D40362J	B06			D02295A	A03			ALL
0174	24		PK		3-6	24-33-13	D40362J	A04			D02295A	C03			ALL
0175	24		PK		3-6	24-33-13	D40362J	B04			D02295A	D03			ALL
0176	24		PK		3-6	24-33-13	D40362J	A05			D02295D	A03			ALL

WIRE LIST

D280A108

91-21-11

Section W0320

Page 5

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice
W0321	286A0321				E3-2 SHELF (continued)										
0177	24		PK	3-6	24-33-13	D40362J	B05			D02295D	B03			ALL	
0178	24		PK	2-10	31-31-15	D02295A	F01			D40426J	4			ALL	
0179	20		G5	2-1	27-53-12	D40468J	A02			D40194J	A01			ALL	
0180	20		G5	2-1	27-53-12	D40468J	B01			D40194J	B01			ALL	
0183	24		PK	3-5	26-14-11	D02295E	K04			D40362J	A03			YC051-YD170	
0185	20		G5	2-1	27-31-11	D42361J	A08			D43030J	B02			ALL	
0186	22		G5	0-6	27-32-11	D03683A	4			GD03207	DC..	1F		ALL	
0187	22		G5	0-6	27-32-11	D03683A	6			GD03207	DC..	1F		ALL	
0188	22		G5	0-6	27-32-11	D03683B	14			GD03209	DC..	1F		ALL	
0189	22		PA	0-6	27-32-21	D03685B	14			GD03213	DC..	1F		ALL	
0190	22		PA	0-6	27-32-21	D03685A	4			GD03211	DC..	1F		ALL	
0191	22		PA	0-6	27-32-21	D03685A	6			GD03211	DC..	1F		ALL	
0192	20		G5	2-7	SPARE	D40426J	7			D45157J	B05			YC051-YC053	
0193	24		PK	2-2	31-31-17	D02295E	K01			D42261J	B05			YC051-YD157	
0194	24		PK	2-2	31-31-17	D02295B	J01			D42261J	B10			YC051-YD157	
0195	22		PA	3-8	31-35-03	D40362J	A10			D43217J	A01			YN236-YR328	
0196	24		PK	2-2	31-35-03	D02295A	F11			D43217J	A10			YN236-YR328	
0197	24		PK	2-2	31-35-03	D02295A	H12			D43217J	B01			YN236-YR328	
0200	24		B6	1-7	21-51-21	D40392J	B14			D43263J	A11			YD158-YR328	
0201	24		PK	2-4	31-31-14	D02295B	D09			TB3201Z	A069	1A		ALL	
0208	24		PK	2-10	31-31-15	D40426J	5			D02295A	G01			YC065-YR328	
0209	24		PK	2-1	31-31-15	D43030J	A02			D02295D	H01			YC065-YR328	
0210	24		B6	2-11	31-31-15	D43022J	A03			D02295D	A07			YC065-YR328	
0213	24		PK	3-0	21-31-24	D40468J	A05			D40446J	A10			ALL	
0215	24		G6	2-4	21-51-14	D43030J	A05			D42261J	B06			YC051-YL999, YN232-YR328	
0215	24		G6	1-8	21-51-14	D43030J	A05			SM00040		W		YN231	
0216	24		G6	2-10	21-51-11	D40908J	A04			D40426J	10			ALL	
0217	24		PK	1-11	21-51-24	D40392J	B04			D42363J	A01			ALL	
0218	24		PK	1-10	21-51-24	D40392J	B05			D40468J	A04			ALL	
0220	20		PA	0-7	23-34-01	D10461	11			D10461	10			YL951-YN260	
0221	24		G6	2-3	22-11-14	D45117J	A04			D03683A	22			ALL	
0223	20		G5	2-3	28-42-11	D40470J	A02			D43022J	A13			ALL	
0224	20		G5	2-3	28-42-11	D40470J	B02			D43022J	B13			ALL	
0226	20		PA	2-5	22-23-12	D41819J	5			TB3201Y	A019	1A		ALL	
0227	24		G6	2-11	22-11-14	D45127J	B02			D03685A	22			ALL	
0228	22		G5	3-6	22-11-18	D45137J	B03			D03669B	K06			ALL	
0229	22		PA	2-3	22-23-12	D03683B	13			TB3201Y	A019	1A		ALL	
0230	22		G5	2-3	22-23-11	D45117J	B01			D03683A	102			ALL	

WIRE LIST

D280A108

91-21-11

Section W0320

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321			E3-2 SHELF (continued)											
0231	22		G5		2-9	22-23-11	D46021J		8		D03685A	102			ALL
0232	22		G5		3-2	22-23-11	D40596J		A07		D03683A	88			ALL
0233	22		G5		3-2	22-23-11	D40596J		B07		D03683A	106			ALL
0234	20		G5		2-4	22-23-11	D40596J		A08		SM00012		W		ALL
0235	20		G5		2-4	22-23-11	D40596J		B08		SM00013		W		ALL
0236	22		G5		1-5	22-23-11	D03683A		93		SM00012		W		ALL
0237	22		G5		1-5	22-23-11	D03683A		12		SM00013		W		ALL
0238	22		G5		2-2	22-23-11	D40025J		A01		D03683A	39			ALL
0239	22		G5		2-4	22-23-11	D40596J		A09		SM00014		W		ALL
0240	22		G5		3-1	22-23-11	D40596J		B09		D03685A	88			ALL
0241	22		G5		1-5	22-23-11	D03683A		24		SM00014		W		ALL
0242	22		G5		1-10	22-23-11	D03685A		106		D03683A	92			ALL
0243	22		G5		1-3	22-23-11	D03685A		93		SM00012		W		ALL
0244	22		G5		1-3	22-23-11	SM00013			W	D03685A	12			ALL
0245	22		G5		1-3	22-23-11	SM00014			W	D03685A	24			ALL
0246	22		G5		2-0	22-23-11	D03685A		92		GD03202	DC..	1A		ALL
0247	22		PA		2-5	27-32-21	D46021J		4		TB3201Y	B033	1A		YC051-YL952, YN231-YN501
0247	22		PA		1-9	27-32-21	D46021J		4		SM00068		W		YL953-YL999, YR301-YR328
0248	22		PA		2-5	27-32-21	D03685B		55		TB3201Y	B033	1A		YC051-YL952, YN231-YN501
0248	22		PA		2-3	27-32-21	D03685B		55		SM00068		W		YL953-YL999, YR301-YR328
0249	22		G5		2-6	27-32-21	D46043J		5		TB3201Y	B011	1A		ALL
0250	22		G5		2-5	27-32-21	D46043J		6		D03685A	10			ALL
0251	22		PA		3-4	27-32-21	D42053J		A07		TB3201Y	B033	1A		YC051-YL952, YN231-YN501
0251	22		PA		1-11	27-32-21	D42053J		A07		SM00068		W		YL953-YL999, YR301-YR328
0252	22		PA		3-1	27-32-21	D42053J		A08		GD03202	AC..	1A		ALL
0253	22		PA		2-9	27-32-21	D43263J		A17		TB3201Y	B033	1A		YC051-YL952, YN231-YN501
0253	22		PA		1-3	27-32-21	D43263J		A17		SM00068		W		YL953-YL999, YR301-YR328
0254	20		PA		1-8	27-32-21	D43263J		B17		GD03204	AC..	1A		ALL
0255	22		PA		1-11	27-32-21	D03685B		56		GD03202	AC..	1A		ALL
0256	22		PA		0-6	27-32-21	D03685B		2		GD03213	DC..	1F		ALL
0257	22		PA		2-0	27-32-21	D03685A		14		GD03202	DC..	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0320

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321		286A0321					E3-2 SHELF (continued)									
0258		22		PA		1-10	27-32-21	D03685A	79			TB3201Y	A015	1A		ALL
0259		22		PA		1-10	27-32-21	D03685A	65			TB3201Y	B013	1A		ALL
0260		22		PA		2-11	27-32-21	D45127J	B01			D03685A	47			ALL
0261		22		PA		3-7	22-23-12	D03683B	1			GD03205	AC..	1A		ALL
0262		22		CQ		2-0	27-32-21	D46021J	6			SM00327		W		YC051-YC055
0262		22		CQ		2-9	27-32-21	D46021J	6			SM00327		W		YC056-YC057
0262		22		G5		2-0	27-32-21	D46021J	6			SM00327		W		YC058-YR328
0263		22		PA		2-9	27-32-21	D40468J	B02			D03685A	20			ALL
0265		24		PK		1-9	27-32-21	TB3201Y	A013	1A		D03685B	19			ALL
0267		22		PA		1-11	27-32-21	TB3201X	B001	1A		D03685A	84			ALL
0268		22		PA		1-9	27-32-21	TB3201Y	B009	1A		D03685B	76			ALL
0269		22		PA		1-10	27-32-21	TB3201X	B003	1A		D03685B	74			ALL
0270		22		G5		2-10	27-24-11	D03685A	39			D40029J	A01			ALL
0273		22		G5		2-10	27-32-11	TB3201Y	A033	1A		D43261J	A14			YC051-YL952, YN231-YN501
0273		22		G5		2-5	27-32-11	SM00066		W		D43261J	A14			YL953-YL999, YR301-YR328
0274		22		G5		2-10	27-32-11	D40053J	A08			TB3201Y	A033	1A		YC051-YL952, YN231-YN501
0274		22		G5		1-7	27-32-11	D40053J	A08			SM00066		W		YL953-YL999, YR301-YR328
0275		22		PA		2-3	27-32-11	D45117J	A01			TB3201Y	B013	1A		ALL
0276		22		PA		2-0	27-32-11	D03683A	65			TB3201Y	B013	1A		ALL
0277		22		PA		2-3	27-32-11	D45117J	B04			TB3201Y	A015	1A		ALL
0278		22		PA		2-0	27-32-11	TB3201Y	A015	1A		D03683A	79			ALL
0279		22		G5		1-8	27-83-11	D40940J	A02			D03683A	5			ALL
0280		22		G5		2-7	27-32-11	TB3201Y	A033	1A		D03683B	55			YC051-YL952, YN231-YN501
0280		22		G5		1-4	27-32-11	SM00066		W		D03683B	55			YL953-YL999, YR301-YR328
0281		22		PA		1-10	27-32-21	TB3201X	B004	1A		D03685B	78			ALL
0282		22		PA		1-9	27-32-21	TB3201X	B005	1A		D03685B	49			ALL
0283		22		PA		1-10	27-32-21	TB3201X	B002	1A		D03685B	34			ALL
0284		22		PA		1-9	27-32-21	TB3201X	A008	1A		D03685B	48			YC051-YL999, YR301-YR328
0284		22		PA		1-9	27-32-21	TB3201Y	B009	1A		D03685B	48			YN231-YN501
0285		22		PA		1-9	27-32-21	TB3201Y	B009	1A		D03685A	100			YC051-YL952
0285		22		PA		1-9	27-32-21	TB3201X	B006	1A		D03685A	100			YL953-YR328
0286		20		PA		1-9	27-32-21	TB3201Y	B009	1A		GD03201	DC..	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0320

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To							
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321			E3-2 SHELF (continued)											
0287	24		PK		2-9	27-32-21	D40468J	A03			D03685A	74			ALL
0288	20		CQ		1-9	23-34-01	D40173J	A03			SM00077		W		YL951-YN260
0289	20		CQ		1-11	23-34-01	D10461	1			SM00077		W		YL951-YN260
0290	24		G6		1-2	29-33-11	D40468J	B09			SM00010		W		ALL
0291	24		G6		1-5	29-33-11	D43046J	A02			SM00010		W		ALL
0294	24		G6		1-2	29-33-11	D40392J	A08			SM00011		W		ALL
0295	24		G6		1-5	29-33-11	D43046J	B02			SM00011		W		ALL
0296	24		G6		2-5	29-33-11	D40350J	B06			SM00008		W		ALL
0297	24		G6		2-5	29-33-11	D40350J	A07			SM00009		W		ALL
0298	24		G6		1-10	29-33-11	SM00008		W		D43022J	A19			ALL
0299	24		G6		1-10	29-33-11	SM00009		W		D43022J	B19			ALL
0300	20		CQ		1-10	23-34-01	D10461	2			GD03201	AC..	1A		YL951-YN260
0301	20		PA		1-10	23-34-01	D10461	16			GD03201	ST..	1A		YL951-YN260
0303	22		G5		2-4	30-31-12	D40596J	A06			D40194J	B03			ALL
0304	22		PA		2-4	30-31-11	D40596J	B04			D40194J	B02			ALL
0305	20		PA		2-4	78-34-21	D40952J	B01			D01458B	17			ALL
0306	20		CQ		2-4	78-34-21	D40952J	B02			D01458B	67			ALL
0307	20		PA		1-8	78-34-21	D01458B	5			GD03203	DC..	1A		ALL
0308	20		CQ		2-0	78-34-21	D01458B	7			TB3201Y	B029	1A		ALL
0309	20		CQ		2-9	78-34-21	D40952J	B03			TB3201Y	B029	1A		ALL
0310	20		CQ		1-11	78-34-21	D01458B	42			D43054J	A03			ALL
0311	20		CQ		2-2	78-34-21	TB3201Y	B029	1A		D43054J	B03			ALL
0312	20		PA		2-8	78-34-21	D40952J	B04			D43054J	A04			ALL
0313	22		G5		2-2	32-41-11	D43054J	B02			D40350J	B07			ALL
0314	20		PA		2-8	78-34-21	D40952J	B05			D43054J	A05			ALL
0315	22		PA		2-0	31-53-11	D03685A	63			D40462J	A18			ALL
0316	22		PA		2-0	31-53-11	D40470J	A03			D40194J	A09			ALL
0317	22		PA		2-10	31-53-11	D40462J	A19			D40194J	B09			ALL
0318	20		CQ		2-8	78-34-21	D40952J	B06			D43054J	B04			ALL
0320	20		CQ		2-2	78-34-11	D40950J	A01			D01458A	67			ALL
0321	20		CQ		2-4	78-34-11	D40950J	A04			TB3201Y	A029	1A		ALL
0322	20		PA		1-8	78-34-11	D01458A	5			GD03203	DC..	1A		ALL
0323	20		CQ		2-0	78-34-11	D01458A	7			TB3201Y	A029	1A		ALL
0324	20		PA		2-2	78-34-11	D40950J	A05			D01458A	17			ALL
0325	20		CQ		1-9	78-34-11	D40950J	A02			D43022J	B04			ALL
0327	22		G5		1-10	32-64-21	D03683A	63			D40594J	B04			ALL
0328	22		PA		2-3	32-64-21	D43030J	B10			D40468J	A01			ALL
0329	20		CQ		1-10	78-34-11	D01458A	42			D43022J	A04			ALL
0330	20		CQ		1-10	23-34-01	D40426J	8			SM00077		W		YL951-YN260

WIRE LIST

D280A108

91-21-11

Section W0320

Page 9

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321				E3-2 SHELF (continued)										
0332	20		PA		2-7	33-25-11	D43030J	B04			D40596J	A02			YC051-YL952, YN231-YN501 YL951-YN260
0333	22		PA		3-2	23-34-01	D10461	56			D40173J	B13			
0334	20		PA		2-4	33-49-11	D40596J	A01			D40194J	B15			ALL
0340	22		PA		3-1	34-33-21	D46021J	5			D03669C	8			ALL
0341	20		PA		1-7	34-33-21	GD03205	ST..	1A		D03669C	2			ALL
0342	22		G5		3-2	27-32-11	D40596J	A03			D03683A	47			ALL
0343	20		PA		1-7	34-33-21	GD03205	AC..	1A		D03669C	3			ALL
0348	24		PK		2-9	34-33-21	D40486J	A01			D03669B	F04			ALL
0349	24		PK		0-7	34-33-21	D03669B	J04			D03669B	J02			ALL
0350	24		PK		0-7	34-33-21	D03669B	E03			D03669B	F02			ALL
0351	24		PK		0-7	34-33-21	D03669B	C05			D03669B	B06			ALL
0352	22		PA		1-9	34-33-21	D03669B	F05			GD03205	DC..	1A		ALL
0353	22		PA		1-9	34-33-21	D03669B	F06			GD03205	DC..	1A		ALL
0354	24		PK		2-5	31-53-11	D40470J	B04			D43054J	A11			ALL
0355	22		PA		2-3	32-64-21	D43030J	A01			D40468J	B05			ALL
0356	24		PK		1-11	27-11-11	D02295D	F07			D43080J	A04			ALL
0357	24		PK		1-11	27-11-11	D02295A	E07			D43080J	A05			ALL
0358	24		G6		2-11	27-21-11	D02295D	G07			TB3201Y	B041	1A		YC051-YD153
0358	24		PK		1-11	27-21-11	D02295D	G07			D40392J	B20			YD154-YR328
0359	24		G6		2-11	27-21-11	D02295A	F07			TB3201Y	A041	1A		YC051-YD153
0359	24		PK		1-11	27-21-11	D02295A	F07			D40392J	A20			YD154-YR328
0360	22		G5		2-3	27-62-11	D40470J	A07			TB3201Y	A047	1A		ALL
0361	22		G5		2-3	27-62-11	D40470J	A08			TB3201Y	B047	1A		ALL
0362	22		G5		2-9	27-62-11	TB3201Y	A047	1A		D43080J	A08			ALL
0363	22		G5		2-9	27-62-11	TB3201Y	B047	1A		D43080J	A09			ALL
0366	24		PK		3-0	31-31-14	D40276J	B01			GD03202	AC..	1A		YC053-YR328
0367	24		PK		2-8	31-31-14	D02295B	D08			GD03202	AC..	1A		YC053-YR328
0368	24		PK		2-8	31-31-14	D40276J	B02			TB3201Z	A069	1A		YC053-YR328
0369	22		G5		2-11	27-62-11	D02295A	C05			TB3201Y	A047	1A		ALL
0370	22		G5		2-11	27-62-11	D02295D	C05			TB3201Y	B047	1A		ALL
0371	24		PK		1-0	27-62-21	SM00015		W		D02295D	G01			ALL
0372	24		PK		2-6	27-62-21	D43054J	B10			SM00015		W		ALL
0373	24		G6		2-9	27-21-11	TB3201Y	A041	1A		D40194J	A19			YC051-YD153
0374	24		G6		2-9	27-21-11	TB3201Y	B041	1A		D40194J	A04			YC051-YD153
0375	22		PA		2-4	27-24-11	D03685B	1			GD03203	AC..	1A		ALL
0376	22		G5		1-11	27-32-11	TB3201Y	A011	1A		D03683A	1			ALL
0377	22		G5		1-8	27-32-11	D03683A	2			GD03201	DC..	1A		ALL
0378	22		G5		1-11	27-32-11	TB3201Y	A011	1A		D03683A	13			ALL

WIRE LIST

D280A108

91-21-11

Section W0320

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321			E3-2 SHELF (continued)											
0380	20		G5		2-3	23-32-21	D02813C		3		D43277J	A10			YC051-YD170
0381	20		PA		1-10	23-32-21	D02813C		4		GD03201	DC..	1A		YC051-YD170
0382	22		PA		1-2	23-32-21	D02813B		33		SM00006		W		YC051-YD170
0384	22		PA		1-2	23-32-21	D02813B		40		SM00006		W		YC051-YD170
0385	22		PA		1-2	23-32-21	D02813B		42		SM00006		W		YC051-YD170
0387	22		PA		1-3	23-32-21	SM00006			W	GD03201	ST..	1A		YC051-YD170
0389	20		PA		1-11	23-32-21	D02813B		36		GD03201	ST..	1A		YC051-YD157
0389	22		PA		1-2	23-32-21	D02813B		36		SM00006		W		YD158-YD170
0390	22		PA		2-3	31-33-01	D40362J		B10		D43215J	A01			ALL
0402	24		PK		3-5	31-31-15	D02295D		J07		D40940J	A07			YC053-YD158
0402	24		PK		3-5	26-16-21	D02295D		J07		D40940J	A07			YL951-YR328
0403	24		PK		3-5	31-31-15	D02295A		H07		D40940J	B07			YC053-YD158
0403	24		PK		3-5	26-16-22	D02295A		H07		D40940J	B07			YL951-YR328
0432	24		G6		3-4	31-35-05	D40940J		A08		D02295B	C10			YL963-YL999, YN236-YR328
0433	24		G6		3-4	31-35-05	D40940J		B02		D02295B	C11			YL963-YL999, YN236-YR328
0434	24		G6		1-11	31-35-05	D40908J		B07		D02295E	C10			YL963-YL999, YN236-YR328
0435	24		G6		1-11	31-35-05	D40908J		B08		D02295E	C11			YL963-YL999, YN236-YR328
0440	22		G5		1-11	27-32-11	TB3201X		B007	1A	D03683B	75			YL951-YR328
0444	22		G5		1-11	27-32-11	TB3201Y		A009	1A	D03683A	33			YL953-YL999, YR301-YR328
0446	22		PA		1-5	27-32-11	TB3201X		A003	1A	SM00024		W		YC067-YD157
0447	22		G5		1-5	27-32-11	TB3201X		A004	1A	SM00024		W		YC051-YC065, YL953-YL999, YR301-YR328
0447	22		PA		1-5	27-32-11	TB3201X		A004	1A	SM00024		W		YC067-YD157
0448	22		PA		1-4	27-32-11	TB3201X		A005	1A	SM00024		W		YC067-YD157
0448	22		G5		1-4	27-32-11	TB3201X		A005	1A	SM00024		W		YL953-YL999, YR301-YR328
0449	22		G5		1-4	27-32-11	SM00024			W	D03683B	75			YC051-YC055
0449	22		G5		1-5	27-32-11	SM00024			W	D03683B	75			YC056-YC065
0449	22		PA		1-4	27-32-11	D03683B		75		SM00024		W		YC067-YD157
0450	22		G5		1-3	27-32-11	GD03201		DC..	1A	SM00024		W		YC051-YC065, YL953-YL999, YR301-YR328
0450	22		PA		1-3	27-32-11	GD03201		DC..	1A	SM00024		W		YC067-YD157

WIRE LIST

D280A108

91-21-11

Section W0320

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321				E3-2 SHELF (continued)										
0462	22		PA		1-5	27-32-21	TB3201X	B003	1A		SM00026		W		YC067-YD157
0463	22		G5		1-5	27-32-21	TB3201X	B004	1A		SM00026		W		YC051-YC065, YL953-YL999, YR301-YR328
0463	22		PA		1-5	27-32-21	TB3201X	B004	1A		SM00026		W		YC067-YD157
0464	22		PA		1-4	27-32-21	TB3201X	B005	1A		SM00026		W		YC067-YD157
0464	22		G5		1-4	27-32-21	TB3201X	B005	1A		SM00026		W		YL953-YR328
0465	22		G5		1-9	27-32-21	SM00026		W		D03685B	75			YC051-YC065
0465	22		PA		1-2	27-32-21	D03685B	75			SM00026		W		YC067-YD157
0465	22		G5		1-4	27-32-21	TB3201X	B008	1A		SM00026		W		YN231-YN501
0466	22		G5		1-3	27-32-21	SM00026		W		GD03201	DC..	1A		YC051-YC065
0466	22		PA		1-3	27-32-21	GD03201	DC..	1A		SM00026		W		YC067-YD157
0466	22		G5		1-3	27-32-21	GD03201	DC..	1A		SM00026		W		YL953-YR328
0469	20		PA		3-9	27-23-11	D40362J	A09			D40276J	B03			YD154-YR328
0470	20		PA		1-5	27-25-11	D40362J	A08			SM00049		W		YD154-YD155
0470	20		PA		3-5	27-25-11	D40362J	A08			D40194J	A20			YD157-YR328
0471	20		PA		2-6	27-25-11	D40362J	B03			SM00050		W		YD154-YD155
0471	20		PA		3-5	27-25-11	D40362J	B03			D40194J	B20			YD157-YR328
0472	20		PA		1-3	27-25-11	D43263J	A11			SM00050		W		YD154-YD155
0473	20		PA		2-6	27-25-11	D40194J	A20			SM00049		W		YD154-YD155
0474	22		PA		3-3	31-31-14	D02295B	D04			D43203J	A07			YD154-YD158
0474	22		PA		2-2	31-31-14	D02295B	D04			D40276J	B07			YL951-YR328
0475	22		PA		1-8	31-31-14	D02295B	D05			GD03204	AC..	1A		YD154-YR328
0476	22		PA		1-11	31-31-14	D43203J	A08			GD03201	AC..	1A		YD154-YD158
0476	22		PA		3-7	31-31-14	D40276J	B08			GD03201	AC..	1A		YL951-YR328
0477	22		PA		2-4	31-31-14	D02295B	D06			TB3201Z	A065	1A		YD154-YR328
0478	22		PA		3-2	31-31-14	D43203J	A09			TB3201Z	A065	1A		YD154-YD158
0478	22		PA		2-8	31-31-14	D40276J	B09			TB3201Z	A065	1A		YL951-YR328
0480	22		G5		1-9	27-32-21	TB3201X	B008	1A		D03685B	75			YL951-YR328
0482	22		PA		2-5	27-62-41	D46043J	1			D03685A	104			YN231-YN501
0483	22		PA		2-5	27-62-41	D46043J	2			D03685A	98			YN231-YN501
0484	22		PA		2-5	27-62-41	D46043J	3			D03685A	99			YN231-YN501
0485	22		PA		2-7	27-62-41	TB3201Y	A047	1A		D03685B	6			YN231-YN501
0488	22		G5		1-9	27-32-21	TB3201Y	B009	1A		D03685A	33			YL953-YL999, YR301-YR328
0490	24		G6		3-3	49-62-11	D45207J	A01			D40908J	B01			ALL
0491	22		G5		1-9	27-32-21	TB3201Y	B011	1A		D03685A	13			ALL
0492	22		G5		1-9	27-32-21	D03685A	1			TB3201Y	B011	1A		ALL
0493	22		PA		2-0	27-32-21	GD03202	DC..	1A		D03685A	2			ALL

WIRE LIST

D280A108

91-21-11

Section W0320

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321				E3-2 SHELF (continued)										
0495	24		G6		2-3	49-52-31	D40908J	A01			D40468J	A09			ALL
0496	24		G6		1-4	21-51-14	SM00040		W		D42261J	B06			YN231
0497	20		G5		1-10	47-30-11	SM00040		W		D40426J	14			YN231
0498	22		PA		1-4	26-16-21	D40486J	B05			SM00048		W		YL951-YR328
0499	20		PA		1-10	47-30-11	SM00048		W		D40426J	15			YL951-YR328
0525	20		CQ		2-8	47-30-11	D42053J	A05			D40486J	B08			YL951-YR328
0526	20		CQ		2-8	47-30-11	D42053J	A06			D40486J	B09			YL951-YR328
0527	20		PA		2-8	47-30-11	D42053J	B10			D40486J	B10			YL951-YR328
0528	20		PA		2-8	47-30-11	D42053J	A09			D40486J	A08			YL951-YR328
0531	20		PA		2-9	33-25-11	TB3201Y	A033	1A		D40596J	A02			YL953-YL999, YR301-YR328
0532	20		PA		3-1	33-25-11	D43030J	B04			TB3201Y	B033	1A		YL953-YL999, YR301-YR328
0533	20		PA		2-7	27-62-11	TB3201Y	A041	1A		D40952J	B13			YL953-YL999, YR301-YR328
0535	20		PA		2-8	27-62-11	D40952J	B14			D43054J	B13			YL953-YL999, YR301-YR328
0536	20		PA		2-8	27-62-11	D43054J	B12			D40952J	B15			YL953-YL999, YR301-YR328
0537	22		PA		2-1	27-62-11	D43080J	B06			D40952J	B16			YL953-YL999, YR301-YR328
0538	22		PA		2-1	27-62-11	D43080J	B07			D40952J	B17			YL953-YL999, YR301-YR328
0539	22		PA		2-7	27-62-11	TB3201Y	A047	1A		D40952J	B18			YL953-YL999, YR301-YR328
0542	20		PA		2-5	27-62-11	TB3201Y	B033	1A		TB3201Y	B041	1A		YL953-YL999, YR301-YR328
0547	24		PK		2-5	31-31-15	TB3201Y	A035	1A		D40426J	1			YN236-YR328
0548	24		PK		3-2	31-35-03	TB3201Y	A035	1A		D43217J	B02			YN236-YR328
0549	24		PK		3-1	31-35-03	D40462J	A06			D43217J	B03			YN236-YR328
0550	24		PK		3-5	31-35-03	D43257J	B06			D43217J	B04			YN236-YR328
0552	24		PK		2-11	23-27-31	D40952J	B19			D45157J	A03			YL951-YL954, YN231-YN235
0553	24		PK		2-11	23-27-31	D40952J	B20			D45157J	A07			YL951-YL954, YN231-YN235
0558	24		PK		2-8	31-31-15	D45102J		3		D02295E	J04			YL963-YL999, YN236-YR328
0559	24		PK		2-8	31-31-15	D45102J		4		D02295B	K03			YL963-YL999, YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W0320

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321		286A0321			E3-2 SHELF (continued)											
0600		22		PA		3-7	22-23-12	D43030J	A04			TB3201Y	B015	1A		ALL
0601		22		PA		1-10	22-23-12	D03685A	35			TB3201Y	B015	1A		ALL
0602		22		PA		2-0	22-23-12	D03683A	35			TB3201Y	B015	1A		ALL
0603		20		G5		2-0	22-23-12	D40025J	A10			GD03201	AC..	1A		ALL
0604		20		G5		2-3	22-23-12	D40025J	A09			TB3201Y	A019	1A		ALL
0605		20		G5		2-1	27-24-11	D40029J	A07			TB3201Z	B069	1A		ALL
0606		20		G5		1-10	27-24-11	D40029J	A08			GD03203	AC..	1A		ALL
0607		20		G5		2-5	27-25-11	D46043J	12			D40194J	A20			YC051-YD153
0607		20		G5		2-5	27-25-11	D46043J	12			SM00049		W		YD154-YD155
0608		20		G5		2-0	27-25-11	D43263J	A11			D40194J	B20			YC051-YD153
0608		20		G5		2-0	27-25-11	SM00050		W		D40194J	B20			YD154-YD155
0700		20		PA		2-3	78-36-21	D01458B	1			D40392J	B13			ALL
0701		22		PA		2-3	78-36-21	D01458B	55			D40392J	A13			ALL
0702		22		PA		1-5	27-32-11	D03683A	48			SM00007		W		ALL
0703		22		PA		1-5	27-32-11	D45117J	A20			SM00007		W		ALL
0704		22		PA		1-3	27-32-21	D03685A	48			SM00007		W		ALL
0707		20		PA		1-8	78-36-11	D01458A	3			GD03203	DC..	1A		ALL
0708		20		PA		1-8	78-36-11	D01458A	4			GD03203	ST..	1A		ALL
0710		20		PA		1-8	78-36-21	D01458B	3			GD03203	DC..	1A		ALL
0711		20		PA		1-8	78-36-21	D01458B	4			GD03203	ST..	1A		ALL
0712		24		PK		0-7	77-31-11	D03228A	A02			D03228A	D13			ALL
0713		24		PK		0-7	77-31-11	D03228A	A03			D03228A	C09			ALL
0714		24		PK		0-7	77-31-11	D03228A	A05			D03228A	C13			YC051-YL999, YN236-YR328
0715		24		PK		0-7	77-31-11	D03228A	A11			D03228A	C13			YN231-YN235
0760		24		G6		1-9	76-21-21	D40470J	A05			D40392J	B12			ALL
0770		24		G6		2-0	77-31-11	D03228C	2			D40392J	B19			ALL
0771		24		PK		1-7	77-31-11	D03228C	3			GD03203	AC..	1A		ALL
0772		24		PK		1-7	77-31-11	D03228C	4			GD03203	AC..	1A		ALL
0773		24		PK		1-10	77-31-11	D03228A	B09			GD03203	DC..	1A		ALL
0774		24		PK		1-9	77-31-21	D03228B	A15			GD03203	ST..	1A		ALL
0775		22		PA		1-11	34-57-21	D40486J	A02			D45127J	A03			ALL
0783		22		PA		2-4	78-36-11	D40596J	B03			D01458A	55			ALL
0784		20		PA		1-9	78-36-11	D41819J	12			D01458A	1			ALL
0790		24		PK		2-1	27-18-11	TB3201Z	A073	1A		TB3201Z	A077	1A		YC051-YD170, YN231-YN260
0790		24		PK		1-6	27-18-11	TB3201Z	A073	1A		TB3201Z	A077	1A		YL951-YL999, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0320

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W0321	286A0321				E3-2 SHELF (continued)											
0791	24		PK		2-1	27-18-11	TB3201Z	B073	1A		TB3201Z	B077	1A		YC051-YD170, YN231-YN260	
0791	24		PK		1-6	27-18-11	TB3201Z	B073	1A		TB3201Z	B077	1A		YL951-YL999, YN501-YR328	
0801	24		PK		2-4	31-31-16	D02295D	A11			M01996	1	1A		ALL	
0802	24		PK		2-4	31-31-16	D02295D	B11			M01996	2	1A		ALL	
0803	24		PK		2-4	31-31-16	D02295D	C11			M01996	3	1A		ALL	
0804	24		PK		2-4	31-31-16	D02295D	D11			M01996	4	1A		ALL	
0805	24		PK		2-4	31-31-16	D02295D	E11			M01996	5	1A		ALL	
0806	24		PK		2-4	31-31-16	D02295D	F11			M01996	6	1A		ALL	
0807	24		PK		2-4	31-31-16	D02295D	G11			M01996	7	1A		ALL	
0808	24		PK		2-4	31-31-16	D02295D	H11			M01996	8	1A		ALL	
0809	24		PK		2-4	31-31-16	D02295D	A09			M01996	13	1A		ALL	
0810	24		PK		2-4	31-31-16	D02295D	B09			M01996	14	1A		ALL	
0811	24		PK		2-4	31-31-16	D02295D	C09			M01996	15	1A		ALL	
0812	24		PK		2-4	31-31-16	D02295D	D09			M01996	16	1A		ALL	
0813	24		PK		2-4	31-31-16	D02295D	E09			M01996	17	1A		ALL	
0814	24		PK		2-4	31-31-16	D02295D	F09			M01996	18	1A		ALL	
0815	24		PK		2-4	31-31-16	D02295D	J11			M01996	19	1A		ALL	
0816	24		PK		2-4	31-31-16	D02295D	G09			M01996	9	1A		ALL	
0817	24		PK		2-4	31-31-16	D02295D	H09			M01996	10	1A		ALL	
0818	24		PK		2-4	31-31-16	D02295D	J09			M01996	11	1A		ALL	
0819	24		PK		2-4	31-31-16	D02295D	K09			M01996	12	1A		ALL	
0820	24		PK		2-4	31-31-16	D02295D	K11			M01996	26	1A		ALL	
0900	22		G5		2-10	29-23-11	D40194J	A02			D40462J	B17			ALL	
0901	24		G6		1-9	29-32-11	D45137J	A01			D43022J	A12			ALL	
0902	24		G6		1-9	29-32-11	D45137J	B01			D43022J	B12			ALL	
0903	22		PA		2-5	27-62-41	D46043J	11			D03685A	104			YC051-YC065	
0904	22		PA		2-5	27-62-41	D46043J	9			D03685A	98			YC051-YC065	
0905	22		PA		2-5	27-62-41	D46043J	10			D03685A	99			YC051-YC065	
0906	22		PA		2-7	27-62-41	TB3201Y	A047	1A		D03685B	6			YC051-YC065	
0950	22		CQ		2-0	31-52-11	D42363J	A06			D02295D	C01			ALL	
0955	20		PA		1-9	78-34-11	D40950J	A06			D43022J	A05			ALL	
0956	20		CQ		2-1	78-34-11	D43022J	B05			TB3201Y	A029	1A		ALL	
0957	20		PA		1-9	78-34-11	D40950J	A03			D43022J	A06			ALL	
1001	22		X1	QC	1-9	31-62-14	D45137J	A19			D43022J	A17			ALL	
1001Z				QC	0-0	31-62-14	D45137J	PERG	1F		D43022J	PERG	1F		ALL	
1002	22		X1	QD	2-1	31-62-24	D40392J	A15			D43046J	A03			ALL	
1002Z				QD	0-0	31-62-24	D40392J	PERG	1F		D43046J	PERG	1F		ALL	

WIRE LIST

D280A108

91-21-11

Section W0320

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321		286A0321				E3-2 SHELF (continued)										
1003		22		X1	GR	1-11	27-62-11	D02295A	B05			D43080J	A06			ALL
1003Z					GR	0-0	27-62-11	D02295A	DED			D43080J	A07			ALL
1004		24		Y1	GS	2-8	31-31-14	D40276J	B02			TB3201Z	A069	1A		YC051-YC052
1004Z					GS	0-0	31-31-14	D40276J	PERG	1F		TB3201Z	DED			YC051-YC052
1073		24		Y1	BH	2-2	31-31-14	D40276J	A01			D02295B	D07			YC053-YR328
1073Z					BH	0-0	31-31-14	D40276J	PERG	1F		D02295B	PERG	1A		YC053-YR328
1780		22		X1	VN	2-3	78-32-61	D01458B	18			D40486J	A05			ALL
1780Z					VN	0-0	78-32-61	D01458B	DED			D40486J	PERG	1F		ALL
1781		22		X1	VM	2-3	78-32-61	D01458B	30			D40486J	A06			ALL
1781Z					VM	0-0	78-32-61	D01458B	DED			D40486J	PERG	1F		ALL
1782		22		CQ		2-5	78-32-51	D01458A	30			D40350J	A01			ALL
1783		22		CQ		2-5	78-32-51	D01458A	18			D40350J	B01			ALL
2001B		24		Y2	AA	3-4	31-31-11	D43219J	A04			TB3201Y	B081	1A		ALL
2001R		24		Y2	AA	0-0	31-31-11	D43219J	A03			TB3201Y	A081	1A		ALL
2001Z					AA	0-0	31-31-11	D43219J	PERG	1F		GB03201	ST..	1A		ALL
2002B		24		Y2	AB	2-1	31-31-11	D02295A	B09			TB3201Y	B081	1A		ALL
2002R		24		Y2	AB	0-0	31-31-11	D02295A	A09			TB3201Y	A081	1A		ALL
2002Z					AB	0-0	31-31-11	D02295A	PERG	1A		GB03201	ST..	1A		ALL
2003B		24		Y2	AC	2-1	31-31-11	D43209J	A05			TB3201Y	B081	1A		ALL
2003R		24		Y2	AC	0-0	31-31-11	D43209J	A04			TB3201Y	A081	1A		ALL
2003Z					AC	0-0	31-31-11	D43209J	PERG	1F		GB03201	ST..	1A		ALL
2004B		24		Y2	AD	3-3	31-31-11	D02295A	J09			D43219J	A06			ALL
2004R		24		Y2	AD	0-0	31-31-11	D02295A	K09			D43219J	A05			ALL
2004Z					AD	0-0	31-31-11	D02295A	PERG	1A		D43219J	PERG	1F		ALL
2005B		24		Y2	AE	2-2	31-31-11	D43209J	A02			D02295A	K11			ALL
2005R		24		Y2	AE	0-0	31-31-11	D43209J	A01			D02295A	J11			ALL
2005Z					AE	0-0	31-31-11	D43209J	PERG	1F		D02295A	PERG	1A		ALL
2006B		24		Y2	AF	2-3	31-35-01	D43261J	B01			D02295E	H10			ALL
2006R		24		Y2	AF	0-0	31-35-01	D43261J	A01			D02295E	H09			ALL
2006Z					AF	0-0	31-35-01	D43261J	PERG	1F		D02295E	PERG	1A		ALL
2007B		24		Y2	AH	2-4	31-35-01	D43261J	B02			D02295A	F15			ALL
2007R		24		Y2	AH	0-0	31-35-01	D43261J	A02			D02295A	E15			ALL
2007Z					AH	0-0	31-35-01	D43261J	PERG	1F		D02295A	PERG	1A		ALL
2008B		24		Y2	AG	3-1	31-35-02	D45137J	B07			D02295E	H06			ALL
2008R		24		Y2	AG	0-0	31-35-02	D45137J	A07			D02295E	H05			ALL
2008Z					AG	0-0	31-35-02	D45137J	PERG	1F		D02295E	PERG	1A		ALL
2009B		22		X2	AL	3-0	34-61-18	TB3201Y	B035	1A		D02295E	H08			YC051-YC058
2009B		22		X2	AL	3-0	31-32-15	TB3201Y	B035	1A		D02295E	H08			YC059-YD157
2009B		22		X2	AL	2-3	31-32-15	D43261J	B05			D02295E	H08			YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0320

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321				E3-2 SHELF (continued)										
2009R	22	X2	AL		0-0	34-61-18	TB3201Y	A035	1A		D02295E	H07			YC051-YC058
2009R	22	X2	AL		0-0	31-32-15	TB3201Y	A035	1A		D02295E	H07			YC059-YD157
2009R	22	X2	AL		0-0	31-32-15	D43261J	B04			D02295E	H07			YD158-YR328
2009Z			AL		0-0	34-61-18	GB03201	ST..	1A		D02295E	PERG	1A		YC051-YC058
2009Z			AL		0-0	31-32-15	GB03201	ST..	1A		D02295E	PERG	1A		YC059-YD157
2009Z			AL		0-0	31-32-15	D43261J	PERG	1F		D02295E	PERG	1A		YD158-YR328
2010B	24	Y2	AK		2-1	31-22-11	D42361J	B17			D02295A	H13			ALL
2010R	24	Y2	AK		0-0	31-22-11	D42361J	A17			D02295A	G13			ALL
2010Z			AK		0-0	31-22-11	D42361J	PERG	1F		D02295A	PERG	1A		ALL
2011B	24	Y2	AM		1-11	31-62-25	D45127J	B13			D02295A	H14			ALL
2011R	24	Y2	AM		0-0	31-62-25	D45127J	A13			D02295A	G14			ALL
2011Z			AM		0-0	31-62-25	D45127J	PERG	1F		D02295A	PERG	1A		ALL
2012B	24	Y2	AN		3-1	34-33-11	D45117J	B10			D02295A	B15			ALL
2012R	24	Y2	AN		0-0	34-33-11	D45117J	A10			D02295A	A15			ALL
2012Z			AN		0-0	34-33-11	D45117J	PERG	1F		D02295A	PERG	1A		ALL
2013B	24	Y2	AO		3-1	31-62-15	D45117J	B08			D02295D	F14			ALL
2013R	24	Y2	AO		0-0	31-62-15	D45117J	A08			D02295D	E14			ALL
2013Z			AO		0-0	31-62-15	D45117J	PERG	1F		D02295D	PERG	1A		ALL
2014B	24	Y2	AP		3-3	49-62-11	D45207J	B06			D02295D	K10			ALL
2014R	24	Y2	AP		0-0	49-62-11	D45207J	A05			D02295D	J10			ALL
2014Z			AP		0-0	49-62-11	D45207J	PERG	1F		D02295D	PERG	1A		ALL
2015B	22	X2	AQ		2-4	34-61-15	D43261J	B07			D02295D	D14			ALL
2015R	22	X2	AQ		0-0	34-61-15	D43261J	A07			D02295D	C14			ALL
2015Z			AQ		0-0	34-61-15	D43261J	PERG	1F		D02295D	PERG	1A		ALL
2016B	24	Y2	AR		3-1	34-61-14	D02295D	B13			TB3201Y	B039	1A		ALL
2016R	24	Y2	AR		0-0	34-61-14	D02295D	A13			TB3201Y	A039	1A		ALL
2016Z			AR		0-0	34-61-14	D02295D	PERG	1A		GB03201	ST..	1A		ALL
2017B	24	Y2	AS		3-1	34-21-14	D02295A	F13			TB3201Y	B031	1A		ALL
2017R	24	Y2	AS		0-0	34-21-14	D02295A	E13			TB3201Y	A031	1A		ALL
2017Z			AS		0-0	34-21-14	D02295A	PERG	1A		GB03201	ST..	1A		ALL
2018B	24	Y2	AT		2-10	34-61-14	TB3201Y	B039	1A		D43261J	B08			ALL
2018R	24	Y2	AT		0-0	34-61-14	TB3201Y	A039	1A		D43261J	A08			ALL
2018Z			AT		0-0	34-61-14	GB03201	ST..	1A		D43261J	PERG	1F		ALL
2021B	24	Y2	AW		3-2	31-35-02	D02295E	H04			D45177J	B07			YC051-YN501
2021B	24	Y2	BT		3-2	31-35-02	D02295E	H04			D45177J	B07			YR301-YR328
2021R	24	Y2	AW		0-0	31-35-02	D02295E	H03			D45177J	A07			YC051-YN501
2021R	24	Y2	BT		0-0	31-35-02	D02295E	H03			D45177J	A07			YR301-YR328
2021Z			AW		0-0	31-35-02	D02295E	PERG	1A		D45177J	PERG	1F		YC051-YN501
2021Z			BT		0-0	31-35-02	D02295E	PERG	1A		D45177J	PERG	1F		YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W0320

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W0321	286A0321	E3-2 SHELF (continued)													
2022B	22	X2	GP	3-3	49-62-11	D40908J	B02		D45207J	A08			ALL		
2022R	22	X2	GP	0-0	49-62-11	D40908J	A02		D45207J	A07			ALL		
2022Z			GP	0-0	49-62-11	D40908J	PERG	1F	D45207J	PERG	1F		ALL		
2023B	22	PB	RT	3-1	31-31-14	GD03202	AC..	1A	D43257J	B02			ALL		
2023R	22	PB	RT	0-0	31-31-14	TB3201Z	B069	1A	D43257J	B01			ALL		
2025B	24	Y2	NA	2-4	27-32-12	D03683A	94		TB3201Z	B021	1A		ALL		
2025R	24	Y2	NA	0-0	27-32-12	D03683A	95		TB3201Z	A021	1A		ALL		
2025Z			NA	0-0	27-32-12	GD03207	ST..	1F	GB03201	ST..	1A		ALL		
2026B	24	Y2	NB	3-4	27-32-12	D02295D	B14		TB3201Z	B021	1A		ALL		
2026R	24	Y2	NB	0-0	27-32-12	D02295D	A14		TB3201Z	A021	1A		ALL		
2026Z			NB	0-0	27-32-12	D02295D	PERG	1A	GB03201	ST..	1A		ALL		
2027B	24	Y2	NC	2-2	27-32-22	D03685A	94		TB3201Z	B025	1A		ALL		
2027R	24	Y2	NC	0-0	27-32-22	D03685A	95		TB3201Z	A025	1A		ALL		
2027Z			NC	0-0	27-32-22	GD03211	ST..	1F	GB03201	ST..	1A		ALL		
2028B	24	Y2	ND	3-4	27-32-22	D02295A	K14		TB3201Z	B025	1A		ALL		
2028R	24	Y2	ND	0-0	27-32-22	D02295A	J14		TB3201Z	A025	1A		ALL		
2028Z			ND	0-0	27-32-22	D02295A	PERG	1A	GB03201	ST..	1A		ALL		
2029B	24	Y2	QX	2-7	34-21-14	D03683B	106		TB3201Y	B031	1A		ALL		
2029R	24	Y2	QX	0-0	34-21-14	D03683B	93		TB3201Y	A031	1A		ALL		
2029Z			QX	0-0	34-21-14	GD03207	ST..	1F	GB03201	ST..	1A		ALL		
2030B	24	Y2	QY	2-10	34-21-14	D42261J	B07		TB3201Y	B031	1A		ALL		
2030R	24	Y2	QY	0-0	34-21-14	D42261J	A07		TB3201Y	A031	1A		ALL		
2030Z			QY	0-0	34-21-14	D42261J	PERG	1F	GB03201	ST..	1A		ALL		
2031B	24	Y2	RA	2-11	31-33-01	D02295D	H02		TB3201Z	B049	1A		ALL		
2031R	24	Y2	RA	0-0	31-33-01	D02295D	G02		TB3201Z	A049	1A		ALL		
2031Z			RA	0-0	31-33-01	D02295D	PERG	1A	GB03201	ST..	1A		ALL		
2032B	24	Y2	RB	2-7	31-35-02	D02295D	D02		TB3201Y	B055	1A		ALL		
2032R	24	Y2	RB	0-0	31-35-02	D02295D	C02		TB3201Y	A055	1A		ALL		
2032Z			RB	0-0	31-35-02	D02295D	PERG	1A	GB03201	ST..	1A		ALL		
2033B	24	Y2	RC	2-10	31-33-01	D43215J	B02		TB3201Z	B049	1A		ALL		
2033R	24	Y2	RC	0-0	31-33-01	D43215J	A02		TB3201Z	A049	1A		ALL		
2033Z			RC	0-0	31-33-01	D43215J	PERG	1F	GB03201	ST..	1A		ALL		
2034B	24	Y2	RD	3-1	31-33-01	D43215J	B03		TB3201Y	B055	1A		ALL		
2034R	24	Y2	RD	0-0	31-33-01	D43215J	A03		TB3201Y	A055	1A		ALL		
2034Z			RD	0-0	31-33-01	D43215J	PERG	1F	GB03201	ST..	1A		ALL		
2035B	24	Y2	RE	2-5	31-35-02	D43261J	A10		TB3201Y	B055	1A		ALL		
2035R	24	Y2	RE	0-0	31-35-02	D43261J	A09		TB3201Y	A055	1A		ALL		
2035Z			RE	0-0	31-35-02	D43261J	PERG	1F	GB03201	ST..	1A		ALL		
2036B	24	Y2	RF	2-7	31-35-02	D42363J	A08		TB3201Y	B055	1A		ALL		

WIRE LIST

D280A108

91-21-11

Section W0320

Page 18

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321			E3-2 SHELF (continued)											
2036R	24	Y2	RF		0-0	31-35-02	D42363J	A07			TB3201Y	A055	1A		ALL
2036Z			RF		0-0	31-35-02	D42363J	PERG	1F		GB03201	ST..	1A		ALL
2037B	24	Y2	KL		3-3	31-31-14	D02295B	F15			D43203J	B02			ALL
2037R	24	Y2	KL		0-0	31-31-14	D02295B	F14			D43203J	B01			ALL
2037Z			KL		0-0	31-31-14	D02295B	DED			D43203J	PERG	1F		ALL
2038B	24	Y2	KM		3-3	31-31-14	D02295B	A02			D43203J	B04			ALL
2038R	24	Y2	KM		0-0	31-31-14	D02295B	A01			D43203J	B03			ALL
2038Z			KM		0-0	31-31-14	D02295B	DED			D43203J	PERG	1F		ALL
2039B	24	Y2	KN		3-3	31-31-14	D02295B	A05			D43203J	B06			ALL
2039R	24	Y2	KN		0-0	31-31-14	D02295B	A04			D43203J	B05			ALL
2039Z			KN		0-0	31-31-14	D02295B	DED			D43203J	PERG	1F		ALL
2040B	24	Y2	KO		3-3	31-31-14	D02295B	B05			D43203J	B08			ALL
2040R	24	Y2	KO		0-0	31-31-14	D02295B	B04			D43203J	B07			ALL
2040Z			KO		0-0	31-31-14	D02295B	DED			D43203J	PERG	1F		ALL
2041B	24	Y2	PB		2-1	34-45-11	D02295D	H14			D42361J	B02			ALL
2041R	24	Y2	PB		0-0	34-45-11	D02295D	G14			D42361J	A02			ALL
2041Z			PB		0-0	34-45-11	D02295D	PERG	1A		D42361J	PERG	1F		ALL
2042B	24	Y2	PC		2-1	34-49-11	D02295D	D13			D42361J	B03			ALL
2042R	24	Y2	PC		0-0	34-49-11	D02295D	C13			D42361J	A03			ALL
2042Z			PC		0-0	34-49-11	D02295D	PERG	1A		D42361J	PERG	1F		ALL
2043B	24	Y2	PK		1-11	22-11-51	D02295D	H13			D45127J	B09			ALL
2043R	24	Y2	PK		0-0	22-11-51	D02295D	G13			D45127J	A09			ALL
2043Z			PK		0-0	22-11-51	D02295D	PERG	1A		D45127J	PERG	1F		ALL
2044B	24	Y2	PF		2-1	22-11-51	D02295A	D14			D42361J	B18			ALL
2044R	24	Y2	PF		0-0	22-11-51	D02295A	C14			D42361J	A18			ALL
2044Z			PF		0-0	22-11-51	D02295A	PERG	1A		D42361J	PERG	1F		ALL
2045B	24	Y2	PA		2-1	22-31-52	D42361J	B01			D02295A	B13			ALL
2045R	24	Y2	PA		0-0	22-31-52	D42361J	A01			D02295A	A13			ALL
2045Z			PA		0-0	22-31-52	D42361J	PERG	1F		D02295A	PERG	1A		ALL
2046B	22	X2	PD		2-1	34-21-15	D02295D	H10			D42361J	B04			ALL
2046R	22	X2	PD		0-0	34-21-15	D02295D	G10			D42361J	A04			ALL
2046Z			PD		0-0	34-21-15	D02295D	PERG	1A		D42361J	PERG	1F		ALL
2047B	24	Y2	PL		3-2	34-21-23	D03683A	68			D43263J	B16			ALL
2047R	24	Y2	PL		0-0	34-21-23	D03683A	55			D43263J	A16			ALL
2047Z			PL		0-0	34-21-23	GD03207	ST..	1F		D43263J	PERG	1F		ALL
2048B	24	Y2	PM		2-11	34-21-23	D03685B	91			D43263J	B15			ALL
2048R	24	Y2	PM		0-0	34-21-23	D03685B	104			D43263J	A15			ALL
2048Z			PM		0-0	34-21-23	GD03211	ST..	1F		D43263J	PERG	1F		ALL
2049B	24	PL	RN		2-9	27-62-14	D42053J	A04			TB3201Z	B073	1A		ALL

WIRE LIST

D280A108

91-21-11
Section W0320
Page 19
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W0321	286A0321	E3-2 SHELF (continued)													
2049R	24	PL	RN	0-0	27-62-14	D42053J	A03		TB3201Z	A073	1A		ALL		
2050B	24	PL	RO	3-6	27-62-14	D40053J	A04		TB3201Z	B073	1A		ALL		
2050R	24	PL	RO	0-0	27-62-14	TB3201Z	A073	1A	D40053J	A03			ALL		
2051B	24	PL	QR	2-2	31-31-14	D42261J	A08		TB3201Z	B073	1A		ALL		
2051R	24	PL	QR	0-0	31-31-14	D42261J	A09		TB3201Z	A073	1A		ALL		
2052B	24	PL	QS	2-2	31-31-14	D42261J	B08		TB3201Z	B073	1A		ALL		
2052R	24	PL	QS	0-0	31-31-14	D42261J	B09		TB3201Z	A073	1A		ALL		
2053B	24	OT	RG	2-4	23-32-21	D43277J	B03		D02813B	58			YC051-YD170		
2053W	24	OT	RG	0-0	23-32-21	D43277J	A03		D02813B	57			YC051-YD170		
2053Z			RG	0-0	23-32-21	D43277J	PERG	1F	GD02813	ST..	2		YC051-YD170		
2054B	24	7P	RH	2-4	23-32-21	D43277J	A04		D02813B	26			YC051-YD157		
2054BN	24	7P	RH	0-0	23-32-21	D43277J	B04		D02813B	27			YC051-YD157		
2054Z			RH	0-0	23-32-21	D43277J	PERG	1F	GD02813	ST..	2		YC051-YD157		
2056B	24	Y2	RJ	2-2	34-21-14	D02813C	2		TB3201Y	B031	1A		YC051-YD170		
2056R	24	Y2	RJ	0-0	34-21-14	D02813C	1		TB3201Y	A031	1A		YC051-YD170		
2056Z			RJ	0-0	34-21-14	GD02813	ST..	2	GB03201	ST..	1A		YC051-YD170		
2057B	24	N6	NK	2-2	34-61-14	D02813C	21		TB3201Y	B039	1A		YC051-YC055		
2057B	24	Y2	NK	2-9	34-61-15	D02813C	22		D43261J	B10			YC056-YD170		
2057R	24	N6	NK	0-0	34-61-14	D02813C	22		TB3201Y	A039	1A		YC051-YC055		
2057R	24	Y2	NK	0-0	34-61-15	D02813C	21		D43261J	B09			YC056-YD170		
2057Z			NK	0-0	34-61-14	GD02813	ST..	2	GB03201	ST..	1A		YC051-YD157		
2057Z			NK	0-0	34-61-15	GD02813	ST..	2	D43261J	PERG	1F		YC056-YD170		
2058B	24	Y2	RS	2-5	34-21-13	D02813B	35		TB3201Y	B043	1A		YC051-YD170		
2058R	24	Y2	RS	0-0	34-21-13	D02813B	34		TB3201Y	A043	1A		YC051-YD170		
2058Z			RS	0-0	34-21-13	GD02813	ST..	2	GB03201	ST..	1A		YC051-YD170		
2059B	22	X2	RP	2-10	23-32-21	D02813B	31		D42261J	B20			YC051-YD157		
2059R	22	X2	RP	0-0	23-32-21	D02813B	30		D42261J	B19			YC051-YD157		
2059Z			RP	0-0	23-32-21	GD02813	ST..	2	D42261J	PERG	1F		YC051-YD157		
2060B	24	Y2	RQ	1-11	23-27-15	D02813B	38		D45157J	B09			YC051-YD157		
2060B	24	Y2	RQ	1-11	23-27-34	D02813B	38		D45157J	B09			YD158-YD170		
2060R	24	Y2	RQ	0-0	23-27-15	D02813B	37		D45157J	A09			YC051-YD157		
2060R	24	Y2	RQ	0-0	23-27-34	D02813B	37		D45157J	A09			YD158-YD170		
2060Z			RQ	0-0	23-27-15	GD02813	ST..	2	D45157J	PERG	1F		YC051-YD157		
2060Z			RQ	0-0	23-27-34	GD02813	ST..	2	D45157J	PERG	1F		YD158-YD170		
2061B	22	X2	RR	1-11	23-32-21	D02813B	44		D45157J	B10			YC051-YD170		
2061R	22	X2	RR	0-0	23-32-21	D02813B	43		D45157J	A10			YC051-YD170		
2061Z			RR	0-0	23-32-21	GD02813	ST..	2	D45157J	PERG	1F		YC051-YD170		
2062B	22	X2	BN	1-9	22-23-11	D03683B	86		D03685A	25			ALL		
2062R	22	X2	BN	0-0	22-23-11	D03683B	94		D03685B	53			ALL		

WIRE LIST

D280A108

91-21-11

Section W0320

Page 20

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To			Effectivity				
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice
W0321	286A0321			E3-2 SHELF (continued)											
2062Z				BN	0-0	22-23-11	GD03209	ST..	1F		GD03213	ST..	1F		ALL
2063B	22	X2		BO	1-9	22-23-11	D03683A	25			D03685B	86			YC051-YN501
2063B	22	X2		BM	1-9	22-23-11	D03683A	25			D03685B	86			YR301-YR328
2063R	22	X2		BO	0-0	22-23-11	D03683B	53			D03685B	94			YC051-YN501
2063R	22	X2		BM	0-0	22-23-11	D03683B	53			D03685B	94			YR301-YR328
2063Z				BO	0-0	22-23-11	GD03209	ST..	1F		GD03213	ST..	1F		YC051-YN501
2063Z				BM	0-0	22-23-11	GD03209	ST..	1F		GD03213	ST..	1F		YR301-YR328
2064B	24	Y2		BP	2-8	31-33-01	D43261J	A19			TB3201Z	B049	1A		ALL
2064R	24	Y2		BP	0-0	31-33-01	D43261J	A18			TB3201Z	A049	1A		ALL
2064Z				BP	0-0	31-33-01	D43261J		PERG 1F		GB03201	ST..	1A		ALL
2065B	24	Y2		BQ	2-10	31-33-01	D42363J	B09			TB3201Z	B049	1A		ALL
2065R	24	Y2		BQ	0-0	31-33-01	D42363J	B08			TB3201Z	A049	1A		ALL
2065Z				BQ	0-0	31-33-01	D42363J		PERG 1F		GB03201	ST..	1A		ALL
2066B	24	Y2		BR	3-3	34-61-24	D43215J	B06			D43261J	B16			ALL
2066R	24	Y2		BR	0-0	34-61-24	D43215J	A06			D43261J	B15			ALL
2066Z				BR	0-0	34-61-24	D43215J		PERG 1F		D43261J		PERG 1F		ALL
2067B	24	Y2		BS	3-2	34-61-24	D43215J	B07			D43263J	B03			ALL
2067R	24	Y2		BS	0-0	34-61-24	D43215J	A07			D43263J	A03			ALL
2067Z				BS	0-0	34-61-24	D43215J		PERG 1F		D43263J		PERG 1F		ALL
2070B	24	Y2		BV	2-5	23-27-32	D43215J	B05			D45177J	B03			YD158-YR328
2070R	24	Y2		BV	0-0	23-27-32	D43215J	A05			D45177J	A03			YD158-YR328
2070Z				BV	0-0	23-27-32	D43215J		PERG 1F		D45177J		PERG 1F		YD158-YR328
2073B	24	Y2		BY	2-2	31-31-14	D40276J	B01			D02295B	D08			YC051-YC052
2073R	24	Y2		BY	0-0	31-31-14	D40276J	A01			D02295B	D07			YC051-YC052
2073Z				BY	0-0	31-31-14	D40276J		PERG 1F		D02295B		PERG 1A		YC051-YC052
2078B	24	Y2		CT	2-5	23-32-21	D43277J	B05			D02813A	14			YC051-YD170
2078R	24	Y2		CT	0-0	23-32-21	D43277J	A05			D02813A	13			YC051-YD170
2078Z				CT	0-0	23-32-21	D43277J	A06			GD02813	ST..	2		YC051-YD170
2090B	24	Y2		BT	3-6	31-35-04	D40350J	B04			D02295A	B04			YL963-YL999, YN501
2090B	24	Y2		DL	3-6	31-35-04	D40350J	B04			D02295A	B04			YN236-YN260, YR301-YR328
2090R	24	Y2		BT	0-0	31-35-04	D40350J	B03			D02295A	A04			YL963-YL999, YN501
2090R	24	Y2		DL	0-0	31-35-04	D40350J	B03			D02295A	A04			YN236-YN260, YR301-YR328
2090Z				BT	0-0	31-35-04	D40350J		PERG 1F		D02295A		PERG 1A		YL963-YL999, YN501
2090Z				DL	0-0	31-35-04	D40350J		PERG 1F		D02295A		PERG 1A		YN236-YN260, YR301-YR328
2099B	20	X2		UY	3-5	27-25-11	D40276J	A10			D45207J	B10			YD154-YR328
2099R	20	X2		UY	0-0	27-25-11	D40276J	A09			D45207J	A10			YD154-YR328

WIRE LIST

D280A108

91-21-11

Section W0320

Page 21

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321			E3-2 SHELF (continued)											
2099Z				UY	0-0	27-25-11	D40276J	PERG	1F		D45207J	PERG	1F		YD154-YR328
2116B	24	Y2		BT	2-11	23-27-39	D40952J	A19			D45177J	B06			YL951-YL954, YN231-YN235
2116R	24	Y2		BT	0-0	23-27-39	D40952J	A20			D45177J	A06			YL951-YL954, YN231-YN235
2116Z				BT	0-0	23-27-39	D40952J	PERG	1F		D45177J	PERG	1F		YL951-YL954, YN231-YN235
2117B	24	Y2		UR	3-0	27-32-22	D40952J	B07			TB3201Z	B025	1A		YD158-YR328
2117R	24	Y2		UR	0-0	27-32-22	D40952J	A07			TB3201Z	A025	1A		YD158-YR328
2117Z				UR	0-0	27-32-22	D40952J	PERG	1F		GB03201	ST..	1A		YD158-YR328
2118B	24	Y2		BU	2-11	23-27-39	D40952J	A18			D45177J	B05			YL951-YL954, YN231-YN235
2118R	24	Y2		BU	0-0	23-27-39	D40952J	A17			D45177J	A05			YL951-YL954, YN231-YN235
2118Z				BU	0-0	23-27-39	D40952J	PERG	1F		D45177J	PERG	1F		YL951-YL954, YN231-YN235
2119B	24	Y2		BW	2-11	23-27-39	D40952J	A16			D45177J	B09			YL951-YL954, YN231-YN235
2119R	24	Y2		BW	0-0	23-27-39	D40952J	A15			D45177J	A09			YL951-YL954, YN231-YN235
2119Z				BW	0-0	23-27-39	D40952J	PERG	1F		D45177J	PERG	1F		YL951-YL954, YN231-YN235
2120B	24	Y2		BX	3-2	31-35-02	D45177J	B08			D02295E	CAP	Y		YN231-YN235
2120R	24	Y2		BX	0-0	31-35-02	D45177J	A08			D02295E	CAP	Y		YN231-YN235
2120Z				BX	0-0	31-35-02	D45177J	PERG	1F		D02295E	DED			YN231-YN235
2123B	24	Y2		PN	1-11	34-55-21	D45127J	B07			D02295A	F14			ALL
2123R	24	Y2		PN	0-0	34-55-21	D45127J	A07			D02295A	E14			ALL
2123Z				PN	0-0	34-55-21	D45127J	PERG	1F		D02295A	PERG	1A		ALL
2126B	24	Y2		DK	2-0	31-35-04	D43263J	B13			D02295A	F06			YL963
2126B	24	Y2		DK	2-0	31-35-04	D43263J	B13			D02295D	F12			YL964-YL999, YN236-YR328
2126R	24	Y2		DK	0-0	31-35-04	D43263J	A13			D02295A	E06			YL963
2126R	24	Y2		DK	0-0	31-35-04	D43263J	A13			D02295D	E12			YL964-YL999, YN236-YR328
2126Z				DK	0-0	31-35-04	D43263J	PERG	1F		D02295A	PERG	1A		YL963
2126Z				DK	0-0	31-35-04	D43263J	PERG	1F		D02295D	PERG	1A		YL964-YL999, YN236-YR328
2130B	24	Y2		PG	3-1	34-51-11	D45117J	B07			D02295A	B14			ALL
2130R	24	Y2		PG	0-0	34-51-11	D45117J	A07			D02295A	A14			ALL

WIRE LIST

D280A108

91-21-11

Section W0320

Page 22

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321				E3-2 SHELF (continued)										
2130Z				PG	0-0	34-51-11	D45117J	PERG	1F		D02295A	PERG	1A		ALL
2131B	24	Y2		PH	3-1	34-31-11	D45117J	B06			D02295D	F13			ALL
2131R	24	Y2		PH	0-0	34-31-11	D45117J	A06			D02295D	E13			ALL
2131Z				PH	0-0	34-31-11	D45117J	PERG	1F		D02295D	PERG	1A		ALL
2132B	24	Y2		AV	3-2	34-55-11	D45137J	B20			D02295D	F10			ALL
2132R	24	Y2		AV	0-0	34-55-11	D45137J	A20			D02295D	E10			ALL
2132Z				AV	0-0	34-55-11	D45137J	PERG	1F		D02295D	PERG	1A		ALL
2133B	22	X2		DM	1-6	31-35-05	D02295E	E07			SM00117		W		YL963-YL999, YN236-YR328
2133R	22	X2		DM	0-0	31-35-05	D02295E	E10			SM00117		W		YL963-YL999, YN236-YR328
2133Z				DM	0-0	31-35-05	D02295E	PERG	1A		SM00119		W		YL963-YL999, YN236-YR328
2134B	22	X2		DN	1-6	31-35-05	D02295E	E08			SM00118		W		YL963-YL999, YN236-YR328
2134R	22	X2		DN	0-0	31-35-05	D02295E	E15			SM00118		W		YL963-YL999, YN236-YR328
2134Z				DN	0-0	31-35-05	D02295E	PERG	1A		SM00119		W		YL963-YL999, YN236-YR328
2135B	20	X2		DO	1-4	31-35-05	SM00118		W		D42261J	A20			YL963-YL999, YN236-YR328
2135R	20	X2		DO	0-0	31-35-05	SM00117		W		D42261J	A19			YL963-YL999, YN236-YR328
2135Z				DO	0-0	31-35-05	SM00119		W		D42261J	PERG	1F		YL963-YL999, YN236-YR328
2137B	22	X2		DP	1-6	31-35-05	D02295B	E07			SM00127		W		YL963-YL999, YN236-YR328
2137R	22	X2		DP	0-0	31-35-05	D02295B	E10			SM00127		W		YL963-YL999, YN236-YR328
2137Z				DP	0-0	31-35-05	D02295B	PERG	1A		SM00129		W		YL963-YL999, YN236-YR328
2138B	22	X2		DT	1-6	31-35-05	D02295B	E08			SM00128		W		YL963-YL999, YN236-YR328
2138R	22	X2		DT	0-0	31-35-05	D02295B	E15			SM00128		W		YL963-YL999, YN236-YR328
2138Z				DT	0-0	31-35-05	D02295B	PERG	1A		SM00129		W		YL963-YL999, YN236-YR328
2139B	20	X2		DU	2-5	31-35-05	SM00128		W		D40940J	B05			YL963-YL999, YN236-YR328

WIRE LIST
D280A108

91-21-11
Section W0320
Page 23
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321			E3-2 SHELF (continued)											
2139R	20	X2	DU		0-0	31-35-05	SM00127		W		D40940J	A05			YL963-YL999, YN236-YR328
2139Z			DU		0-0	31-35-05	SM00129		W		D40940J	PERG	1F		YL963-YL999, YN236-YR328
2150B	22	PB	MB		3-0	31-53-11	D43030J	B09			D40462J	A20			ALL
2150R	22	PB	MB		0-0	31-53-11	D43030J	A09			D40462J	B20			ALL
2151B	24	Y2	AX		2-1	32-41-11	D40940J	B08			D43054J	A01			ALL
2151R	24	Y2	AX		0-0	32-41-11	D40940J	A09			D43054J	B01			ALL
2151Z			AX		0-0	32-41-11	D40940J	B09			D43054J	A02			ALL
2152B	22	PB	XY		3-1	31-31-14	D43257J	A05			GD03202	AC..	1A		ALL
2152R	22	PB	XY		0-0	31-31-14	D43257J	A04			TB3201Z	B069	1A		ALL
2153B	24	M5	XV		1-8	32-41-11	D40594J	B08			D43022J	B01			ALL
2153R	24	M5	XV		0-0	32-41-11	D40594J	B07			D43022J	A01			ALL
2153ZI			XV		0-0	32-41-11	D40594J	B09			D43022J	A02			ALL
2153ZO			XV		0-0	32-41-11	D40594J	DED			D43022J	DED			ALL
2158B	24	Y2	NP		1-7	32-31-11	D40462J	B14			D43054J	A10			ALL
2158R	24	Y2	NP		0-0	32-31-11	D40462J	B15			D43054J	B09			ALL
2158Z			NP		0-0	32-31-11	D40462J	DED			D43054J	DED			ALL
2159B	24	Y2	NQ		1-6	32-31-11	D40462J	B12			D43022J	B09			ALL
2159R	24	Y2	NQ		0-0	32-31-11	D40462J	B13			D43022J	A09			ALL
2159Z			NQ		0-0	32-31-11	D40462J	DED			D43022J	DED			ALL
2160B	22	PB	BA		3-1	31-31-14	D43257J	A07			GD03202	AC..	1A		ALL
2160R	22	PB	BA		0-0	31-31-14	D43257J	A06			TB3201Z	B069	1A		ALL
2161B	22	X2	NE		1-7	32-64-11	D43054J	A08			D40462J	B08			ALL
2161R	22	X2	NE		0-0	32-64-11	D43054J	B07			D40462J	B09			ALL
2161Z			NE		0-0	32-64-11	D43054J	DED			D40462J	DED			ALL
2162B	22	X2	NF		1-7	32-64-11	D43054J	A09			D40462J	B10			ALL
2162R	22	X2	NF		0-0	32-64-11	D43054J	B08			D40462J	B11			ALL
2162Z			NF		0-0	32-64-11	D43054J	DED			D40462J	DED			ALL
2163B	22	X2	NG		1-6	32-64-11	D40462J	B06			D43022J	A11			ALL
2163R	22	X2	NG		0-0	32-64-11	D40462J	B07			D43022J	B11			ALL
2163Z			NG		0-0	32-64-11	D40462J	DED			D43022J	DED			ALL
2164B	22	X2	NH		1-6	32-64-11	D40462J	B04			D43022J	B10			ALL
2164R	22	X2	NH		0-0	32-64-11	D40462J	B05			D43022J	A10			ALL
2164Z			NH		0-0	32-64-11	D40462J	DED			D43022J	DED			ALL
2165B	24	Y2	VA		2-8	34-21-13	TB3201Y	B043	1A		D03685A	68			YC051-YD170
2165B	24	Y2	VA		3-1	34-21-13	D42261J	B03			D03685A	68			YL951-YR328
2165R	24	Y2	VA		0-0	34-21-13	TB3201Y	A043	1A		D03685A	55			YC051-YD170
2165R	24	Y2	VA		0-0	34-21-13	D42261J	A03			D03685A	55			YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0320

Page 24

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321				E3-2 SHELF (continued)										
2165Z				VA	0-0	34-21-13	GB03201	ST..	1A		GD03211	ST..	1F		YC051-YD170
2165Z				VA	0-0	34-21-13	D42261J	PERG	1F		GD03211	ST..	1F		YL951-YR328
2166B	24	Y2		VB	3-2	34-21-13	D42261J	B04			D03683B	91			ALL
2166R	24	Y2		VB	0-0	34-21-13	D42261J	A04			D03683B	104			ALL
2166Z				VB	0-0	34-21-13	D42261J	PERG	1F		GD03207	ST..	1F		ALL
2167B	24	Y2		VC	2-8	34-61-14	D03683A	42			TB3201Y	B039	1A		ALL
2167R	24	Y2		VC	0-0	34-61-14	D03683A	29			TB3201Y	A039	1A		ALL
2167Z				VC	0-0	34-61-14	GD03207	ST..	1F		GB03201	ST..	1A		ALL
2168B	24	Y2		VD	3-0	34-61-14	D03685A	42			D43263J	B04			ALL
2168R	24	Y2		VD	0-0	34-61-14	D03685A	29			D43263J	A04			ALL
2168Z				VD	0-0	34-61-14	GD03211	ST..	1F		D43263J	PERG	1F		ALL
2169B	24	Y2		VE	2-8	34-21-13	D42261J	B03			TB3201Y	B043	1A		YC051-YD170
2169R	24	Y2		VE	0-0	34-21-13	D42261J	A03			TB3201Y	A043	1A		YC051-YD170
2169Z				VE	0-0	34-21-13	D42261J	PERG	1F		GB03201	ST..	1A		YC051-YD170
2170B	24	Y2		LY	2-11	34-21-24	D43263J	B09			D03685B	106			ALL
2170R	24	Y2		LY	0-0	34-21-24	D43263J	A09			D03685B	93			ALL
2170Z				LY	0-0	34-21-24	D43263J	PERG	1F		GD03211	ST..	1F		ALL
2173B	24	Y2		XA	1-11	34-33-21	D45127J	B04			TB3201Y	B083	1A		ALL
2173R	24	Y2		XA	0-0	34-33-21	D45127J	A04			TB3201Y	A083	1A		ALL
2173Z				XA	0-0	34-33-21	D45127J	PERG	1F		GB03201	ST..	1A		ALL
2174B	24	Y2		XB	2-4	34-33-21	D03669B	B03			TB3201Y	B083	1A		ALL
2174R	24	Y2		XB	0-0	34-33-21	D03669B	B02			TB3201Y	A083	1A		ALL
2174Z				XB	0-0	34-33-21	D03669B	PERG	1A		GB03201	ST..	1A		ALL
2175B	24	Y2		XC	1-11	34-33-21	D42363J	B04			TB3201Y	B083	1A		ALL
2175R	24	Y2		XC	0-0	34-33-21	D42363J	A04			TB3201Y	A083	1A		ALL
2175Z				XC	0-0	34-33-21	D42363J	PERG	1F		GB03201	ST..	1A		ALL
2176B	24	Y2		XD	1-11	34-33-21	D42363J	B05			TB3201Z	B085	1A		ALL
2176R	24	Y2		XD	0-0	34-33-21	D42363J	A05			TB3201Z	A085	1A		ALL
2176Z				XD	0-0	34-33-21	D42363J	PERG	1F		GB03201	ST..	1A		ALL
2177B	24	Y2		XE	2-0	34-33-21	D45127J	B15			TB3201Z	B085	1A		ALL
2177R	24	Y2		XE	0-0	34-33-21	D45127J	A15			TB3201Z	A085	1A		ALL
2177Z				XE	0-0	34-33-21	D45127J	PERG	1F		GB03201	ST..	1A		ALL
2178B	24	Y2		XF	2-4	34-33-21	D03669B	G03			TB3201Z	B085	1A		ALL
2178R	24	Y2		XF	0-0	34-33-21	D03669B	G02			TB3201Z	A085	1A		ALL
2178Z				XF	0-0	34-33-21	D03669B	PERG	1A		GB03201	ST..	1A		ALL
2179B	24	Y2		XG	2-0	34-33-21	D45127J	B20			TB3201Z	B085	1A		ALL
2179R	24	Y2		XG	0-0	34-33-21	D45127J	A20			TB3201Z	A085	1A		ALL
2179Z				XG	0-0	34-33-21	D45127J	PERG	1F		GB03201	ST..	1A		ALL
2180B	24	Y2		XH	2-1	34-33-21	D02295D	B15			TB3201Z	B085	1A		ALL

WIRE LIST

D280A108

91-21-11
Section W0320
Page 25
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321		286A0321					E3-2 SHELF (continued)									
2180R		24		Y2	XH	0-0	34-33-21	D02295D	A15			TB3201Z	A085	1A		ALL
2180Z					XH	0-0	34-33-21	D02295D	PERG	1A		GB03201	ST..	1A		ALL
2181B		24		Y2	BB	2-0	34-41-11	D45127J	B08			TB3201Z	B085	1A		ALL
2181R		24		Y2	BB	0-0	34-41-11	D45127J	A08			TB3201Z	A085	1A		ALL
2181Z					BB	0-0	34-41-11	D45127J	PERG	1F		GB03201	ST..	1A		ALL
2182B		24		Y2	EV	1-7	34-21-24	D40392J	B02			D43263J	B06			YC051-YD157
2182R		24		Y2	EV	0-0	34-21-24	D40392J	B01			D43263J	A06			YC051-YD157
2182Z					EV	0-0	34-21-24	D40392J	PERG	1F		D43263J	PERG	1F		YC051-YD157
2183B		24		Y2	MN	2-11	73-24-12	D40908J	B03			D40462J	B01			ALL
2183R		24		Y2	MN	0-0	73-24-12	D40908J	A03			D40462J	B02			ALL
2183Z					MN	0-0	73-24-12	D40908J	PERG	1F		D40462J	PERG	1F		ALL
2184B		24		Y2	BC	3-1	77-31-11	D02295A	D13			TB3201Y	B037	1A		ALL
2184R		24		Y2	BC	0-0	77-31-11	D02295A	C13			TB3201Y	A037	1A		ALL
2184Z					BC	0-0	77-31-11	D02295A	PERG	1A		GB03201	ST..	1A		ALL
2185B		24		Y2	BD	2-7	77-31-11	D03228A	D06			TB3201Y	B037	1A		ALL
2185R		24		Y2	BD	0-0	77-31-11	D03228A	C06			TB3201Y	A037	1A		ALL
2185Z					BD	0-0	77-31-11	D03228A	PERG	1A		GB03201	ST..	1A		ALL
2186B		24		Y2	BE	2-10	77-31-11	D40726J	A04			TB3201Y	B037	1A		YC051-YL954, YN231-YN235
2186B		24		Y2	BE	2-9	77-31-11	D40446J	A04			TB3201Y	B037	1A		YL955-YL999, YN236-YR328
2186R		24		Y2	BE	0-0	77-31-11	D40726J	B04			TB3201Y	A037	1A		YC051-YL954, YN231-YN235
2186R		24		Y2	BE	0-0	77-31-11	D40446J	B04			TB3201Y	A037	1A		YL955-YL999, YN236-YR328
2186Z					BE	0-0	77-31-11	D40726J	PERG	1F		GB03201	ST..	1A		YC051-YL954, YN231-YN235
2186Z					BE	0-0	77-31-11	D40446J	PERG	1F		GB03201	ST..	1A		YL955-YL999, YN236-YR328
2187B		24		Y2	BF	3-2	77-31-11	D03228A	D10			D40726J	A05			YC051-YL954, YN231-YN235
2187B		24		Y2	BF	3-1	77-31-11	D03228A	D10			D40446J	A07			YL955-YL999, YN236-YR328
2187R		24		Y2	BF	0-0	77-31-11	D03228A	C10			D40726J	B05			YC051-YL954, YN231-YN235
2187R		24		Y2	BF	0-0	77-31-11	D03228A	C10			D40446J	B07			YL955-YL999, YN236-YR328
2187Z					BF	0-0	77-31-11	D03228A	PERG	1A		D40726J	PERG	1F		YC051-YL954, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W0320

Page 26

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321				E3-2 SHELF (continued)										
2187Z				BF	0-0	77-31-11	D03228A	PERG	1A		D40446J	PERG	1F		YL955-YL999, YN236-YR328
2188B	24	Y2	BG		3-2	77-31-11	D03228A	B08			D40726J	A06			YC051-YL954, YN231-YN235
2188B	24	Y2	BG		3-1	77-31-11	D03228A	B08			D40446J	A03			YL955-YL999, YN236-YR328
2188R	24	Y2	BG		0-0	77-31-11	D03228A	A08			D40726J	B06			YC051-YL954, YN231-YN235
2188R	24	Y2	BG		0-0	77-31-11	D03228A	A08			D40446J	B03			YL955-YL999, YN236-YR328
2188Z			BG		0-0	77-31-11	D03228A	PERG	1A		D40726J	PERG	1F		YC051-YL954, YN231-YN235
2188Z			BG		0-0	77-31-11	D03228A	PERG	1A		D40446J	PERG	1F		YL955-YL999, YN236-YR328
2189B	22	VX	PR		3-2	77-31-11	D03228A	A01			D40726J	A01			YC051-YL954, YN231-YN235
2189B	22	VX	PR		3-1	77-31-11	D03228A	A01			D40446J	A01			YL955-YL999, YN236-YR328
2189W	22	VX	PR		0-0	77-31-11	D03228A	B01			D40726J	B01			YC051-YL954, YN231-YN235
2189W	22	VX	PR		0-0	77-31-11	D03228A	B01			D40446J	B01			YL955-YL999, YN236-YR328
2189Z			PR		0-0	77-31-11	D03228A	PERG	1A		D40726J	A02			YC051-YL954, YN231-YN235
2189Z			PR		0-0	77-31-11	D03228A	PERG	1A		D40446J	A02			YL955-YL999, YN236-YR328
2190B	22	VX	PS		2-7	77-31-11	D03228A	A04			D40594J	A03			ALL
2190W	22	VX	PS		0-0	77-31-11	D03228A	B04			D40594J	B03			ALL
2190Z			PS		0-0	77-31-11	D03228A	PERG	1A		D40594J	A04			ALL
2191B	24	Y2	QQ		2-0	77-31-21	D03228B	D10			D45127J	B05			ALL
2191R	24	Y2	QQ		0-0	77-31-21	D03228B	C10			D45127J	A05			ALL
2191Z			QQ		0-0	77-31-21	D03228B	PERG	1A		D45127J	PERG	1F		ALL
2192B	24	Y2	WR		2-0	77-31-21	D03228B	B08			D45127J	B06			ALL
2192R	24	Y2	WR		0-0	77-31-21	D03228B	A08			D45127J	A06			ALL
2192Z			WR		0-0	77-31-21	D03228B	PERG	1A		D45127J	PERG	1F		ALL
2193B	22	VX	UH		2-4	77-31-21	D03228B	A01			D43080J	A01			ALL
2193W	22	VX	UH		0-0	77-31-21	D03228B	B01			D43080J	A02			ALL
2193Z			UH		0-0	77-31-21	D03228B	PERG	1A		D43080J	A03			ALL
2194B	22	VX	QT		2-4	77-31-21	D03228B	A04			D43080J	B08			ALL

WIRE LIST

D280A108

91-21-11

Section W0320

Page 27

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321		286A0321					E3-2 SHELF (continued)									
2194W		22		VX	QT	0-0	77-31-21	D03228B	B04			D43080J	B09			ALL
2194Z					QT	0-0	77-31-21	D03228B	PERG	1A		D43080J	B10			ALL
2195B		22		PB	BL	2-7	78-36-11	D40446J	A05			D01458A	39			ALL
2195R		22		PB	BL	0-0	78-36-11	D40446J	B05			D01458A	40			ALL
2196B		22		PB	BK	2-7	78-36-11	D40446J	A06			D01458A	27			ALL
2196R		22		PB	BK	0-0	78-36-11	D40446J	B06			D01458A	28			ALL
2197B		22		X2	MV	2-1	78-36-11	D01458A	52			D40594J	A05			ALL
2197R		22		X2	MV	0-0	78-36-11	D01458A	53			D40594J	B05			ALL
2197Z					MV	0-0	78-36-11	D01458A	DED			D40594J	DED			ALL
2198B		22		X2	MW	2-1	78-36-11	D01458A	14			D40594J	A06			ALL
2198R		22		X2	MW	0-0	78-36-11	D01458A	15			D40594J	B06			ALL
2198Z					MW	0-0	78-36-11	D01458A	DED			D40594J	DED			ALL
2199B		22		PB	MY	1-10	78-36-11	D01458A	43			D43022J	B06			ALL
2199R		22		PB	MY	0-0	78-36-11	D01458A	44			D43022J	A07			ALL
2200B		22		PB	MK	1-10	78-36-11	D01458A	8			D43022J	B07			ALL
2200R		22		PB	MK	0-0	78-36-11	D01458A	9			D43022J	A08			ALL
2201B		22		PB	OJ	2-3	78-36-21	D01458B	39			D40392J	A09			ALL
2201R		22		PB	OJ	0-0	78-36-21	D01458B	40			D40392J	A10			ALL
2202B		22		X2	OK	2-2	78-36-21	D01458B	52			D45127J	B17			ALL
2202R		22		X2	OK	0-0	78-36-21	D01458B	53			D45127J	A17			ALL
2202Z					OK	0-0	78-36-21	D01458B	DED			D45127J	DED			ALL
2203B		22		PB	OL	2-3	78-36-21	D01458B	27			D40392J	A11			ALL
2203R		22		PB	OL	0-0	78-36-21	D01458B	28			D40392J	A12			ALL
2204B		22		X2	OM	2-2	78-36-21	D01458B	14			D45127J	B18			ALL
2204R		22		X2	OM	0-0	78-36-21	D01458B	15			D45127J	A18			ALL
2204Z					OM	0-0	78-36-21	D01458B	DED			D45127J	DED			ALL
2211B		24		Y2	QK	3-2	22-11-51	D03683B	79			D42361J	B09			ALL
2211R		24		Y2	QK	0-0	22-11-51	D03683B	66			D42361J	A09			ALL
2211Z					QK	0-0	22-11-51	GD03207	ST..	1F		D42361J	PERG	1F		ALL
2212B		24		Y2	QL	3-0	22-11-51	D42361J	B10			D03685B	79			ALL
2212R		24		Y2	QL	0-0	22-11-51	D42361J	A10			D03685B	66			ALL
2212Z					QL	0-0	22-11-51	D42361J	PERG	1F		GD03211	ST..	1F		ALL
2213B		24		Y2	CP	2-2	31-35-03	D02295A	F10			D43217J	A03			YN236-YR328
2213R		24		Y2	CP	0-0	31-35-03	D02295A	E10			D43217J	A02			YN236-YR328
2213Z					CP	0-0	31-35-03	D02295A	PERG	1A		D43217J	PERG	1F		YN236-YR328
2214B		24		Y2	CQ	2-2	31-35-03	D02295A	D10			D43217J	A05			YN236-YR328
2214R		24		Y2	CQ	0-0	31-35-03	D02295A	C10			D43217J	A04			YN236-YR328
2214Z					CQ	0-0	31-35-03	D02295A	PERG	1A		D43217J	PERG	1F		YN236-YR328
2215B		24		Y2	CR	2-2	31-35-03	D02295A	K02			D43217J	A07			YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W0320

Page 28

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From				To						
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321			E3-2 SHELF (continued)											
2215R	24	Y2	CR		0-0	31-35-03	D02295A	J02			D43217J	A06			YN236-YR328
2215Z			CR		0-0	31-35-03	D02295A	PERG	1A		D43217J	PERG	1F		YN236-YR328
2216B	24	Y2	CS		2-2	31-35-03	D02295A	F09			D43217J	A09			YN236-YR328
2216R	24	Y2	CS		0-0	31-35-03	D02295A	E09			D43217J	A08			YN236-YR328
2216Z			CS		0-0	31-35-03	D02295A	PERG	1A		D43217J	PERG	1F		YN236-YR328
2217B	24	Y2	AU		2-2	31-35-03	D02295A	J12			D43217J	B06			YN236-YR328
2217R	24	Y2	AU		0-0	31-35-03	D02295A	K12			D43217J	B05			YN236-YR328
2217Z			AU		0-0	31-35-03	D02295A	PERG	1A		D43217J	PERG	1F		YN236-YR328
2221B	24	Y2	AJ		3-1	22-23-12	TB3201Y	B059	1A		D03683A	53			YC051-YN501
2221B	24	Y2	AJ		3-1	22-23-12	D03683A	53			TB3201Y	B059	1A		YR301-YR328
2221R	24	Y2	AJ		0-0	22-23-12	TB3201Y	A059	1A		D03683A	54			YC051-YN501
2221R	24	Y2	AJ		0-0	22-23-12	D03683A	54			TB3201Y	A059	1A		YR301-YR328
2221Z			AJ		0-0	22-23-12	GB03201	ST..	1A		GD03207	ST..	1F		YC051-YN501
2221Z			AJ		0-0	22-23-12	GD03207	ST..	1F		GB03201	ST..	1A		YR301-YR328
2222B	24	Y2	AY		3-1	22-23-12	TB3201Y	B057	1A		D03683A	58			YC051-YN501
2222B	24	Y2	AY		3-1	22-23-12	D03683A	58			TB3201Y	B057	1A		YR301-YR328
2222R	24	Y2	AY		0-0	22-23-12	TB3201Y	A057	1A		D03683A	57			YC051-YN501
2222R	24	Y2	AY		0-0	22-23-12	D03683A	57			TB3201Y	A057	1A		YR301-YR328
2222Z			AY		0-0	22-23-12	GB03201	ST..	1A		GD03207	ST..	1F		YC051-YN501
2222Z			AY		0-0	22-23-12	GD03207	ST..	1F		GB03201	ST..	1A		YR301-YR328
2223B	22	X2	MD		2-1	22-23-12	D40025J	A08			D03683B	41			ALL
2223R	22	X2	MD		0-0	22-23-12	D40025J	A07			D03683B	40			ALL
2223Z			MD		0-0	22-23-12	D40025J	PERG	1F		GD03209	ST..	1F		ALL
2225B	24	Y2	CL		2-6	22-23-12	TB3201Y	B059	1A		D42363J	B07			YC051-YN501
2225B	24	Y2	CL		2-6	22-23-12	D42363J	B07			TB3201Y	B059	1A		YR301-YR328
2225R	24	Y2	CL		0-0	22-23-12	TB3201Y	A059	1A		D42363J	B06			YC051-YN501
2225R	24	Y2	CL		0-0	22-23-12	D42363J	B06			TB3201Y	A059	1A		YR301-YR328
2225Z			CL		0-0	22-23-12	GB03201	ST..	1A		D42363J	PERG	1F		YC051-YN501
2225Z			CL		0-0	22-23-12	D42363J	PERG	1F		GB03201	ST..	1A		YR301-YR328
2226B	22	X2	CA		2-1	22-23-12	D45117J	B13			TB3201Y	B017	1A		YC051-YL959, YN231-YN235
2226R	22	X2	CA		0-0	22-23-12	D45117J	A13			TB3201Y	A017	1A		YC051-YL959, YN231-YN235
2226Z			CA		0-0	22-23-12	GB03201	ST..	1A		D45117J	PERG	1F		YC051-YL959, YN231-YN235
2228B	24	Y2	CO		2-8	22-23-12	TB3201Y	B057	1A		D45117J	B19			YC051-YN501
2228B	24	Y2	CO		2-8	22-23-12	D45117J	B19			TB3201Y	B057	1A		YR301-YR328
2228R	24	Y2	CO		0-0	22-23-12	TB3201Y	A057	1A		D45117J	A19			YC051-YN501
2228R	24	Y2	CO		0-0	22-23-12	D45117J	A19			TB3201Y	A057	1A		YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W0320

Page 29

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W0321	286A0321	E3-2 SHELF (continued)													
2228Z			CO	0-0	22-23-12	GB03201	ST..	1A	D45117J	PERG	1F		YC051-YN501		
2228Z			CO	0-0	22-23-12	D45117J	PERG	1F	GB03201	ST..	1A		YR301-YR328		
2301B	24	Y2	AZ	3-1	23-27-12	D02295E	H02		D45157J	B08			YC051-YD157		
2301B	24	Y2	AZ	1-10	23-27-33	D02295E	H02		D45147J	B18			YD158-YR328		
2301R	24	Y2	AZ	0-0	23-27-12	D02295E	H01		D45157J	A08			YC051-YD157		
2301R	24	Y2	AZ	0-0	23-27-33	D02295E	H01		D45147J	A18			YD158-YR328		
2301Z			AZ	0-0	23-27-12	D02295E	PERG	1A	D45157J	PERG	1F		YC051-YD157		
2301Z			AZ	0-0	23-27-33	D02295E	PERG	1A	D45147J	PERG	1F		YD158-YN501		
2301Z			AZ	0-0	23-27-33	D02295E	PERG	1F	D45147J	PERG	1F		YR301-YR328		
2302B	22	X2	CG	2-3	34-61-18	TB3201Y	B035	1A	D45117J	B12			YC051-YC058		
2302B	22	X2	CG	2-10	31-32-15	TB3201Y	B035	1A	D43261J	B05			YC059-YD157		
2302R	22	X2	CG	0-0	34-61-18	TB3201Y	A035	1A	D45117J	A12			YC051-YC058		
2302R	22	X2	CG	0-0	31-32-15	TB3201Y	A035	1A	D43261J	B04			YC059-YD157		
2302Z			CG	0-0	34-61-18	GB03201	ST..	1A	D45117J	PERG	1F		YC051-YC058		
2302Z			CG	0-0	31-32-15	GB03201	ST..	1A	D43261J	PERG	1F		YC059-YD157		
2303B	22	X2	CH	2-5	34-61-18	TB3201Y	B035	1A	D45177J	B08			YC051-YC058		
2303R	22	X2	CH	0-0	34-61-18	TB3201Y	A035	1A	D45177J	A08			YC051-YC058		
2303Z			CH	0-0	34-61-18	GB03201	ST..	1A	D45177J	PERG	1F		YC051-YC058		
2304B	22	X2	CI	2-3	34-61-18	TB3201Y	B035	1A	D02813B	9			YC051-YC058		
2304B	22	X2	CI	2-3	31-32-15	TB3201Y	B035	1A	D02813B	9			YC059-YD157		
2304R	22	X2	CI	0-0	34-61-18	TB3201Y	A035	1A	D02813B	8			YC051-YC058		
2304R	22	X2	CI	0-0	31-32-15	TB3201Y	A035	1A	D02813B	8			YC059-YD157		
2304Z			CI	0-0	34-61-18	GB03201	ST..	1A	GD02813	ST..	2		YC051-YC058		
2304Z			CI	0-0	31-32-15	GB03201	ST..	1A	GD02813	ST..	2		YC059-YD157		
2305B	24	Y2	CJ	3-3	34-61-23	D02295D	F02		D45177J	B10			ALL		
2305R	24	Y2	CJ	0-0	34-61-23	D02295D	E02		D45177J	A10			ALL		
2305Z			CJ	0-0	34-61-23	D02295D	PERG	1A	D45177J	PERG	1F		ALL		
2306B	24	Y2	CE	1-11	34-61-23	D02295D	K02		D45147J	B09			ALL		
2306R	24	Y2	CE	0-0	34-61-23	D02295D	J02		D45147J	A09			ALL		
2306Z			CE	0-0	34-61-23	D02295D	PERG	1A	D45147J	PERG	1F		ALL		
2307B	22	X2	FA	3-2	23-34-01	D10461	67		D40173J	B01			YL951-YN260		
2307R	22	X2	FA	0-0	23-34-01	D10461	66		D40173J	A01			YL951-YN260		
2307Z			FA	0-0	23-34-01	D10461		AE	D40173J			AA	YL951-YN260		
2308B	22	X2	FB	3-2	23-34-01	D10461	63		D40173J	B02			YL951-YN260		
2308R	22	X2	FB	0-0	23-34-01	D10461	62		D40173J	A02			YL951-YN260		
2308Z			FB	0-0	23-34-01	D10461		AE	D40173J			AA	YL951-YN260		
2309B	22	X2	FC	3-2	23-34-01	D10461	65		D40173J	B04			YL951-YN260		
2309R	22	X2	FC	0-0	23-34-01	D10461	64		D40173J	A04			YL951-YN260		
2309Z			FC	0-0	23-34-01	D10461		AE	D40173J			AA	YL951-YN260		

WIRE LIST

D280A108

91-21-11

Section W0320

Page 30

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321				E3-2 SHELF (continued)										
2310B	22	X2	FD		3-2	23-34-01	D10461	61			D40173J	B05			YL951-YN260
2310R	22	X2	FD		0-0	23-34-01	D10461	60			D40173J	A05			YL951-YN260
2310Z			FD		0-0	23-34-01	D10461			AE	D40173J		AA		YL951-YN260
2311B	22	X2	FE		3-2	23-34-01	D10461	54			D40173J	B06			YL951-YN260
2311R	22	X2	FE		0-0	23-34-01	D10461	53			D40173J	A06			YL951-YN260
2311Z			FE		0-0	23-34-01	D10461			AE	D40173J		AB		YL951-YN260
2312B	22	X2	FF		3-2	23-34-01	D10461	50			D40173J	B07			YL951-YN260
2312R	22	X2	FF		0-0	23-34-01	D10461	49			D40173J	A07			YL951-YN260
2312Z			FF		0-0	23-34-01	D10461			AE	D40173J		AB		YL951-YN260
2313B	22	X2	FG		3-2	23-34-01	D10461	52			D40173J	B09			YL951-YN260
2313R	22	X2	FG		0-0	23-34-01	D10461	51			D40173J	A09			YL951-YN260
2313Z			FG		0-0	23-34-01	D10461			AE	D40173J		AB		YL951-YN260
2314B	22	X2	FH		3-2	23-34-01	D10461	48			D40173J	B10			YL951-YN260
2314R	22	X2	FH		0-0	23-34-01	D10461	47			D40173J	A10			YL951-YN260
2314Z			FH		0-0	23-34-01	D10461			AE	D40173J		AB		YL951-YN260
2315B	22	X2	FI		3-2	23-34-01	D10461	13			D40173J	B11			YL951-YN260
2315R	22	X2	FI		0-0	23-34-01	D10461	12			D40173J	A11			YL951-YN260
2315Z			FI		0-0	23-34-01	D10461			AE	D40173J		AC		YL951-YN260
2316B	22	X2	FJ		3-2	23-34-01	D10461	38			D40173J	B12			YL951-YN260
2316R	22	X2	FJ		0-0	23-34-01	D10461	37			D40173J	A12			YL951-YN260
2316Z			FJ		0-0	23-34-01	D10461			AE	D40173J		AC		YL951-YN260
2317B	22	X2	FK		3-2	23-34-01	D10461	40			D40173J	B14			YL951-YN260
2317R	22	X2	FK		0-0	23-34-01	D10461	39			D40173J	A14			YL951-YN260
2317Z			FK		0-0	23-34-01	D10461			AE	D40173J		AC		YL951-YN260
2318B	22	X2	FL		3-2	23-34-01	D10461	36			D40173J	B15			YL951-YN260
2318R	22	X2	FL		0-0	23-34-01	D10461	35			D40173J	A15			YL951-YN260
2318Z			FL		0-0	23-34-01	D10461			AE	D40173J		AC		YL951-YN260
2319B	22	X2	FM		3-2	23-34-01	D10461	29			D40173J	B16			YL951-YN260
2319R	22	X2	FM		0-0	23-34-01	D10461	28			D40173J	A16			YL951-YN260
2319Z			FM		0-0	23-34-01	D10461			AE	D40173J		AD		YL951-YN260
2320B	22	X2	FN		3-2	23-34-01	D10461	25			D40173J	B17			YL951-YN260
2320R	22	X2	FN		0-0	23-34-01	D10461	24			D40173J	A17			YL951-YN260
2320Z			FN		0-0	23-34-01	D10461			AE	D40173J		AD		YL951-YN260
2321B	22	X2	FO		3-2	23-34-01	D10461	27			D40173J	B19			YL951-YN260
2321R	22	X2	FO		0-0	23-34-01	D10461	26			D40173J	A19			YL951-YN260
2321Z			FO		0-0	23-34-01	D10461			AE	D40173J		AD		YL951-YN260
2322B	22	X2	FP		3-2	23-34-01	D10461	23			D40173J	B20			YL951-YN260
2322R	22	X2	FP		0-0	23-34-01	D10461	22			D40173J	A20			YL951-YN260
2322Z			FP		0-0	23-34-01	D10461			AE	D40173J		AD		YL951-YN260

WIRE LIST

D280A108

91-21-11

Section W0320

Page 31

Dec 19/2011



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321			E3-2 SHELF (continued)											
2500B	24	Y2	CF		1-11	34-31-21	D02295A	K13			D45127J	B10			ALL
2500R	24	Y2	CF		0-0	34-31-21	D02295A	J13			D45127J	A10			ALL
2500Z			CF		0-0	34-31-21	D02295A	PERG	1A		D45127J	PERG	1F		ALL
2501B	24	Y2	CK		1-11	34-51-21	D02295D	K13			D45127J	B11			ALL
2501R	24	Y2	CK		0-0	34-51-21	D02295D	J13			D45127J	A11			ALL
2501Z			CK		0-0	34-51-21	D02295D	PERG	1A		D45127J	PERG	1F		ALL
2503B	22	X2	TV		0-9	27-32-11	D40025J	B04			SM00323		W		YC051-YC052, YC054-YC055, YC058-YN501
2503B	22	X2	TV		0-7	27-32-11	D40025J	B04			SM00323		W		YC053
2503B	22	X2	TV		3-0	27-32-11	D40025J	B04			SM00323		W		YC056-YC057
2503B	22	X2	TV		1-4	27-32-11	D40025J	B04			SM00323		W		YR301-YR328
2503R	22	X2	TV		0-0	27-32-11	D40025J	A04			SM00321		W		ALL
2503Z			TV		0-0	27-32-11	D40025J	PERG	1F		SM00325		W		ALL
2505B	22	X2	TW		2-2	27-32-11	D03683A	105			SM00323		W		YC051-YC055, YC059-YN501
2505B	22	X2	TW		3-0	27-32-11	D03683A	105			SM00323		W		YC056-YC058
2505B	22	X2	TW		1-5	27-32-11	D03683A	105			SM00323		W		YR301-YR328
2505R	22	X2	TW		0-0	27-32-11	D03683A	7			SM00321		W		ALL
2505Z			TW		0-0	27-32-11	GD03209	ST..	1F		SM00325		W		ALL
2506B	22	X2	TT		2-2	27-32-21	D40029J	B07			SM00329		W		YC051-YC055, YC058-YR328
2506B	22	X2	TT		3-0	27-32-21	D40029J	B07			SM00329		W		YC056-YC057
2506R	22	X2	TT		0-0	27-32-21	D40029J	B06			SM00327		W		ALL
2506Z			TT		0-0	27-32-21	D40029J	PERG	1F		SM00331		W		ALL
2507B	22	X2	TU		1-3	27-32-21	D03685A	105			SM00329		W		YC051-YC055, YC058-YR328
2507B	22	X2	TU		3-0	27-32-21	D03685A	105			SM00329		W		YC056-YC057
2507R	22	X2	TU		0-0	27-32-21	D03685A	7			SM00327		W		ALL
2507Z			TU		0-0	27-32-21	GD03211	ST..	1F		SM00331		W		ALL
2516B	24	Y2	YZ		2-9	31-31-13	D45102J	2			D02295D	H12			YL963-YL999, YN236-YR328
2516R	24	Y2	YZ		0-0	31-31-13	D45102J	1			D02295D	G12			YL963-YL999, YN236-YR328
2516Z			YZ		0-0	31-31-13	D45102J	S/R			D02295D	PERG	1A		YL963-YL999, YN236-YR328
2600R	20	X5	AI		2-1	26-12-11	D43022J	B03			D40350J	A06			ALL
2600Z			AI		0-0	26-12-11	D43022J	DED			D40350J	DED			ALL
2700B	24	PL	CM		2-9	27-18-11	D42053J	A02			TB3201Z	B077	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0320

Page 32

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321			E3-2 SHELF (continued)											
2700R	24	PL	CM		0-0	27-18-11	D42053J	A01			TB3201Z	A077	1A		ALL
2701B	24	PL	LC		3-7	27-18-11	D40053J	A02			TB3201Z	B077	1A		ALL
2701R	24	PL	LC		0-0	27-18-11	D40053J	A01			TB3201Z	A077	1A		ALL
2702B	24	PL	LE		2-0	27-62-37	D40468J	B10			TB3201Z	B073	1A		ALL
2702R	24	PL	LE		0-0	27-62-37	D40468J	A10			TB3201Z	A073	1A		ALL
2704B	24	Y2	LH		2-0	27-28-11	D43263J	B01			D40194J	A07			ALL
2704R	24	Y2	LH		0-0	27-28-11	D43263J	A20			D40194J	A08			ALL
2704Z			LH		0-0	27-28-11	D43263J	DED			D40194J	DED			ALL
2705B	24	PL	LK		2-4	27-28-11	D40194J	B04			TB3201Z	B077	1A		ALL
2705R	24	PL	LK		0-0	27-28-11	D40194J	B05			TB3201Z	A077	1A		ALL
2706B	24	PL	LL		2-4	27-38-11	D40194J	A10			TB3201Z	B077	1A		ALL
2706R	24	PL	LL		0-0	27-38-11	D40194J	A11			TB3201Z	A077	1A		ALL
2707B	24	PL	LN		2-4	27-38-11	D40194J	A12			TB3201Z	B077	1A		ALL
2707R	24	PL	LN		0-0	27-38-11	D40194J	A13			TB3201Z	A077	1A		ALL
2708B	24	PL	LO		2-4	27-48-11	D40194J	A14			TB3201Z	B077	1A		ALL
2708R	24	PL	LO		0-0	27-48-11	D40194J	A15			TB3201Z	A077	1A		ALL
2709B	24	Y2	UA		2-11	22-23-12	TB3201Y	B057	1A		D03685A	53			ALL
2709R	24	Y2	UA		0-0	22-23-12	TB3201Y	A057	1A		D03685A	54			ALL
2709Z			UA		0-0	22-23-12	GB03201	ST..	1A		GD03211	ST..	1F		YC051-YN501
2709Z			UA		0-0	22-23-12	GD03211	ST..	1F		GB03201	ST..	1A		YR301-YR328
2710B	22	PB	UB		1-11	78-36-21	D01458B	43			D43054J	B05			ALL
2710R	22	PB	UB		0-0	78-36-21	D01458B	44			D43054J	A06			ALL
2711B	22	PB	UC		1-11	78-36-21	D01458B	8			D43054J	B06			ALL
2711R	22	PB	UC		0-0	78-36-21	D01458B	9			D43054J	A07			ALL
2713B	24	Y2	UE		2-1	27-32-12	D45117J	B18			TB3201Z	B021	1A		ALL
2713R	24	Y2	UE		0-0	27-32-12	D45117J	A18			TB3201Z	A021	1A		ALL
2713Z			UE		0-0	27-32-12	D45117J	PERG	1F		GB03201	ST..	1A		ALL
2714B	24	Y2	UF		2-1	27-32-12	D45117J	B16			TB3201Z	B021	1A		ALL
2714R	24	Y2	UF		0-0	27-32-12	D45117J	A16			TB3201Z	A021	1A		ALL
2714Z			UF		0-0	27-32-12	D45117J	PERG	1F		GB03201	ST..	1A		ALL
2715B	24	Y2	UL		2-1	27-32-12	D45117J	B14			TB3201Z	B021	1A		ALL
2715R	24	Y2	UL		0-0	27-32-12	D45117J	A14			TB3201Z	A021	1A		ALL
2715Z			UL		0-0	27-32-12	D45117J	PERG	1F		GB03201	ST..	1A		ALL
2716B	24	Y2	UK		2-2	31-62-15	D03683B	64			D45117J	B09			ALL
2716R	24	Y2	UK		0-0	31-62-15	D03683B	65			D45117J	A09			ALL
2716Z			UK		0-0	31-62-15	GD03207	ST..	1F		D45117J	PERG	1F		ALL
2717B	24	Y2	UM		3-0	27-32-12	D42361J	A15			TB3201Z	B021	1A		ALL
2717R	24	Y2	UM		0-0	27-32-12	D42361J	A13			TB3201Z	A021	1A		ALL
2717Z			UM		0-0	27-32-12	D42361J	PERG	1F		GB03201	ST..	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0320

Page 33

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321		286A0321				E3-2 SHELF (continued)										
2719B		24		Y2	KA	2-11	22-23-12	TB3201Y	B059	1A		D03685A	58			YC051-YN501
2719B		24		Y2	KA	2-11	22-23-12	D03685A	58			TB3201Y	B059	1A		YR301-YR328
2719R		24		Y2	KA	0-0	22-23-12	TB3201Y	A059	1A		D03685A	57			YC051-YN501
2719R		24		Y2	KA	0-0	22-23-12	D03685A	57			TB3201Y	A059	1A		YR301-YR328
2719Z					KA	0-0	22-23-12	GB03201	ST..	1A		GD03211	ST..	1F		YC051-YN501
2719Z					KA	0-0	22-23-12	GD03211	ST..	1F		GB03201	ST..	1A		YR301-YR328
2720B		22		X2	PE	2-9	27-24-11	D03685B	41			D40029J	A03			ALL
2720R		22		X2	PE	0-0	27-24-11	D03685B	40			D40029J	A02			ALL
2720Z					PE	0-0	27-24-11	GD03213	ST..	1F		D40029J	PERG	1F		ALL
2725B		24		Y2	EB	2-7	27-81-41	TB3201Y	B045	1A		D42361J	B16			ALL
2725R		24		Y2	EB	0-0	27-81-41	TB3201Y	A045	1A		D42361J	A16			ALL
2725Z					EB	0-0	27-81-41	GB03201	ST..	1A		D42361J	PERG	1F		ALL
2746B		24		Y2	KC	3-2	31-62-15	D45137J	B02			D02295D	K04			YL951-YR328
2746R		24		Y2	KC	0-0	31-62-15	D45137J	A02			D02295D	J04			YL951-YR328
2746Z					KC	0-0	31-62-15	D45137J	PERG	1F		D02295D	PERG	1A		YL951-YR328
2747B		24		Y2	KD	3-2	31-62-15	D45137J	B05			D02295D	B06			YL951-YR328
2747R		24		Y2	KD	0-0	31-62-15	D45137J	A05			D02295D	A06			YL951-YR328
2747Z					KD	0-0	31-62-15	D45137J	PERG	1F		D02295D	PERG	1A		YL951-YR328
2748B		24		Y2	KE	1-11	31-62-25	D45147J	B03			D02295A	B06			YL951-YR328
2748R		24		Y2	KE	0-0	31-62-25	D45147J	A03			D02295A	A06			YL951-YR328
2748Z					KE	0-0	31-62-25	D45147J	PERG	1F		D02295A	PERG	1A		YL951-YR328
2749B		24		Y2	KF	1-11	31-62-25	D45147J	B04			D02295A	D06			YL951-YR328
2749R		24		Y2	KF	0-0	31-62-25	D45147J	A04			D02295A	C06			YL951-YR328
2749Z					KF	0-0	31-62-25	D45147J	PERG	1F		D02295A	PERG	1A		YL951-YR328
2750B		24		Y2	KB	2-10	31-62-25	D03685B	64			D45127J	B12			ALL
2750R		24		Y2	KB	0-0	31-62-25	D03685B	65			D45127J	A12			ALL
2750Z					KB	0-0	31-62-25	GD03211	ST..	1F		D45127J	PERG	1F		ALL
2751B		24		Y2	VI	2-11	27-81-41	TB3201Y	B045	1A		D02295D	K14			ALL
2751R		24		Y2	VI	0-0	27-81-41	TB3201Y	A045	1A		D02295D	J14			ALL
2751Z					VI	0-0	27-81-41	GB03201	ST..	1A		D02295D	PERG	1A		ALL
2752B		24		Y2	VG	2-6	27-81-41	D45137J	B17			TB3201Y	B045	1A		ALL
2752R		24		Y2	VG	0-0	27-81-41	D45137J	A17			TB3201Y	A045	1A		ALL
2752Z					VG	0-0	27-81-41	D45137J	PERG	1F		GB03201	ST..	1A		ALL
2753B		24		Y2	KV	3-0	27-32-22	D43263J	B05			TB3201Z	B025	1A		ALL
2753R		24		Y2	KV	0-0	27-32-22	D43263J	A05			TB3201Z	A025	1A		ALL
2753Z					KV	0-0	27-32-22	D43263J	PERG	1F		GB03201	ST..	1A		ALL
2754B		24		Y2	KW	3-0	27-32-22	D43263J	B12			TB3201Z	B025	1A		ALL
2754R		24		Y2	KW	0-0	27-32-22	D43263J	A12			TB3201Z	A025	1A		ALL
2754Z					KW	0-0	27-32-22	D43263J	PERG	1F		GB03201	ST..	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0320

Page 34

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321				E3-2 SHELF (continued)										
2755B	24	Y2	KY		3-3	27-32-22	D45147J	B10			TB3201Z	B025	1A		ALL
2755R	24	Y2	KY		0-0	27-32-22	D45147J	A10			TB3201Z	A025	1A		ALL
2755Z			KY		0-0	27-32-22	D45147J	PERG	1F		GB03201	ST..	1A		ALL
2756B	24	Y2	KX		3-3	27-32-22	D45147J	B12			TB3201Z	B025	1A		ALL
2756R	24	Y2	KX		0-0	27-32-22	D45147J	A12			TB3201Z	A025	1A		ALL
2756Z			KX		0-0	27-32-22	D45147J	PERG	1F		GB03201	ST..	1A		ALL
2757B	24	Y2	TA		2-11	27-32-22	D40392J	B18			TB3201Z	B025	1A		YC051-YD157
2757R	24	Y2	TA		0-0	27-32-22	D40392J	B17			TB3201Z	A025	1A		YC051-YD157
2757Z			TA		0-0	27-32-22	D40392J	PERG	1F		GB03201	ST..	1A		YC051-YD157
2763B	24	Y2	NJ		2-7	23-27-14	D45177J	B04			TB3201Z	B049	1A		YC051-YD157
2763B	24	Y2	NJ		2-7	31-33-01	D45177J	B04			TB3201Z	B049	1A		YD158-YR328
2763R	24	Y2	NJ		0-0	23-27-14	D45177J	A04			TB3201Z	A049	1A		YC051-YD157
2763R	24	Y2	NJ		0-0	31-33-01	D45177J	A04			TB3201Z	A049	1A		YD158-YR328
2763Z			NJ		0-0	23-27-14	D45177J	PERG	1F		GB03201	ST..	1A		YC051-YD157
2763Z			NJ		0-0	31-33-01	D45177J	PERG	1F		GB03201	ST..	1A		YD158-YR328
2764B	24	Y2	NI		2-5	23-27-14	D43215J	B04			D45177J	B03			YC051-YD157
2764R	24	Y2	NI		0-0	23-27-14	D43215J	A04			D45177J	A03			YC051-YD157
2764Z			NI		0-0	23-27-14	D43215J	PERG	1F		D45177J	PERG	1F		YC051-YD157
2819B	24	Y2	XK		1-11	22-11-51	D02295D	D15			D45127J	B14			ALL
2819R	24	Y2	XK		0-0	22-11-51	D02295D	C15			D45127J	A14			ALL
2819Z			XK		0-0	22-11-51	D02295D	PERG	1A		D45127J	PERG	1F		ALL
2820B	24	Y2	XP		2-1	22-11-51	D42361J	B19			D02295A	D15			ALL
2820R	24	Y2	XP		0-0	22-11-51	D42361J	A19			D02295A	C15			ALL
2820Z			XP		0-0	22-11-51	D42361J	PERG	1F		D02295A	PERG	1A		ALL
3001B	24	PM	WA		2-6	31-31-14	TB3201Y	B063	1A		D02295B	A09			ALL
3001R	24	PM	WA		0-0	31-31-14	TB3201Y	B061	1A		D02295B	A07			ALL
3001Y	24	PM	WA		0-0	31-31-14	TB3201Y	A063	1A		D02295B	A08			ALL
3004B	24	PM	WD		2-11	31-31-14	D43257J	A01			TB3201Y	B063	1A		ALL
3004R	24	PM	WD		0-0	31-31-14	D43257J	A02			TB3201Y	B061	1A		ALL
3004Y	24	PM	WD		0-0	31-31-14	D43257J	A03			TB3201Y	A063	1A		ALL
3005B	24	PM	WE		3-2	31-31-14	D43257J	A09			D02295E	A06			ALL
3005R	24	PM	WE		0-0	31-31-14	D43257J	A08			D02295E	A04			ALL
3005Y	24	PM	WE		0-0	31-31-14	D43257J	A10			D02295E	A05			ALL
3006B	24	PM	WF		3-2	31-31-14	D43257J	B04			D02295E	A09			ALL
3006R	24	PM	WF		0-0	31-31-14	D43257J	B03			D02295E	A07			ALL
3006Y	24	PM	WF		0-0	31-31-14	D43257J	B05			D02295E	A08			ALL
3008B	24	PM	WJ		2-2	31-31-14	D42261J	B17			D02295E	B09			ALL
3008R	24	PM	WJ		0-0	31-31-14	D42261J	B16			D02295E	B07			ALL
3008Y	24	PM	WJ		0-0	31-31-14	D42261J	B18			D02295E	B08			ALL

WIRE LIST

D280A108

91-21-11

Section W0320

Page 35

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321			E3-2 SHELF (continued)											
3009B	24		PM	DA	2-2	31-31-14	D42261J	A17			D02295E	B06			ALL
3009R	24		PM	DA	0-0	31-31-14	D42261J	A16			D02295E	B04			ALL
3009Y	24		PM	DA	0-0	31-31-14	D42261J	A18			D02295E	B05			ALL
3010B	22		PC	DB	2-11	27-24-11	D03685B	82			TB3201Y	B063	1A		ALL
3010R	22		PC	DB	0-0	27-24-11	D03685B	81			TB3201Y	B061	1A		ALL
3010Y	22		PC	DB	0-0	27-24-11	D03685B	95			TB3201Y	A063	1A		ALL
3011B	24		PM	RK	3-7	27-62-14	D40053J	B02			D02295E	B12			ALL
3011R	24		PM	RK	0-0	27-62-14	D40053J	B01			D02295E	B10			ALL
3011Y	24		PM	RK	0-0	27-62-14	D40053J	B03			D02295E	B11			ALL
3012B	24		PM	RL	2-3	27-62-14	D42053J	B05			D02295B	B12			ALL
3012R	24		PM	RL	0-0	27-62-14	D42053J	B04			D02295B	B10			ALL
3012Y	24		PM	RL	0-0	27-62-14	D42053J	B06			D02295B	B11			ALL
3013B	24		PM	RM	2-2	27-62-37	D40468J	B08			D02295B	B09			ALL
3013R	24		PM	RM	0-0	27-62-37	D40468J	A08			D02295B	B07			ALL
3013Y	24		PM	RM	0-0	27-62-37	D40468J	B07			D02295B	B08			ALL
3224B	22		X3	MC	2-3	22-23-12	D40025J	B02			TB3201Y	B017	1A		YC051-YL959, YN231-YN235
3224R	22		X3	MC	0-0	22-23-12	D40025J	B01			TB3201Y	A017	1A		YC051-YL959, YN231-YN235
3224Y	22		X3	MC	0-0	22-23-12	D40025J	B03			TB3201Y	B019	1A		YC051-YL959, YN231-YN235
3224Z				MC	0-0	22-23-12	D40025J	PERG	1F		GB03201	ST..	1A		YC051-YL959, YN231-YN235
3225B	22		X3	DD	2-3	22-23-12	D03683B	16			TB3201Y	B017	1A		YC051-YL959, YN231-YN235
3225B	22		X3	DD	2-1	22-23-12	D03683B	16			D40025J	B02			YL963-YL999, YN236-YR328
3225R	22		X3	DD	0-0	22-23-12	D03683B	30			TB3201Y	A017	1A		YC051-YL959, YN231-YN235
3225R	22		X3	DD	0-0	22-23-12	D03683B	30			D40025J	B01			YL963-YL999, YN236-YR328
3225Y	22		X3	DD	0-0	22-23-12	D03683B	29			TB3201Y	B019	1A		YC051-YL959, YN231-YN235
3225Y	22		X3	DD	0-0	22-23-12	D03683B	29			D40025J	B03			YL963-YL999, YN236-YR328
3225Z				DD	0-0	22-23-12	GD03209	ST..	1F		GB03201	ST..	1A		YC051-YL959, YN231-YN235
3225Z				DD	0-0	22-23-12	GD03209	ST..	1F		D40025J	PERG	1F		YL963-YL999, YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W0320

Page 36

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321			E3-2 SHELF (continued)											
3700B	24		PM	LB	2-3	27-18-11	D42053J	B02			D02295E	A15			ALL
3700R	24		PM	LB	0-0	27-18-11	D42053J	B01			D02295E	A13			ALL
3700Y	24		PM	LB	0-0	27-18-11	D42053J	B03			D02295E	A14			ALL
3701B	24		PM	LD	3-7	27-18-11	D40053J	A06			D02295B	B03			ALL
3701R	24		PM	LD	0-0	27-18-11	D40053J	A05			D02295B	B01			ALL
3701Y	24		PM	LD	0-0	27-18-11	D40053J	A07			D02295B	B02			ALL
3705B	24		PM	LJ	2-3	27-28-11	D40194J	B07			D02295E	B15			ALL
3705R	24		PM	LJ	0-0	27-28-11	D40194J	B06			D02295E	B13			ALL
3705Y	24		PM	LJ	0-0	27-28-11	D40194J	B08			D02295E	B14			ALL
3706B	24		PM	LM	2-3	27-38-11	D40194J	A16			D02295E	A12			ALL
3706R	24		PM	LM	0-0	27-38-11	D40194J	A17			D02295E	A10			ALL
3706Y	24		PM	LM	0-0	27-38-11	D40194J	A18			D02295E	A11			ALL
3707B	24		PM	DH	2-3	27-38-11	D40194J	B16			D02295B	A12			ALL
3707R	24		PM	DH	0-0	27-38-11	D40194J	B17			D02295B	A10			ALL
3707Y	24		PM	DH	0-0	27-38-11	D40194J	B18			D02295B	A11			ALL
3711B	24		PM	DR	2-3	27-48-11	D40194J	B12			D02295E	A03			ALL
3711R	24		PM	DR	0-0	27-48-11	D40194J	B13			D02295E	A01			ALL
3711Y	24		PM	DR	0-0	27-48-11	D40194J	B14			D02295E	A02			ALL
3712B	22		PC	DS	3-7	27-32-21	D42053J	B08			D03685B	97			ALL
3712R	22		PC	DS	0-0	27-32-21	D42053J	B07			D03685B	99			ALL
3712Y	22		PC	DS	0-0	27-32-21	D42053J	B09			D03685B	98			ALL
3713B	22		PC	DW	2-11	27-32-21	D43263J	B19			D03685B	72			ALL
3713R	22		PC	DW	0-0	27-32-21	D43263J	B18			D03685B	71			ALL
3713Y	22		PC	DW	0-0	27-32-21	D43263J	B20			D03685B	58			ALL
3721B	22		X3	DY	2-9	27-24-11	D03685B	16			D40029J	A05			ALL
3721R	22		X3	DY	0-0	27-24-11	D03685B	30			D40029J	A04			ALL
3721Y	22		X3	DY	0-0	27-24-11	D03685B	29			D40029J	A06			ALL
3721Z				DY	0-0	27-24-11	GD03213	ST..	1F		D40029J	PERG	1F		ALL
3732B	22		X3	MA	1-11	27-32-11	D40053J	B05			D03683B	97			ALL
3732R	22		X3	MA	0-0	27-32-11	D40053J	B04			D03683B	99			ALL
3732Y	22		X3	MA	0-0	27-32-11	D40053J	B06			D03683B	98			ALL
3732Z				MA	0-0	27-32-11	D40053J	DED			D03683B	DED			ALL
3733B	22		X3	LW	3-3	27-32-11	D43261J	A16			D03683B	71			ALL
3733R	22		X3	LW	0-0	27-32-11	D43261J	A15			D03683B	72			ALL
3733Y	22		X3	LW	0-0	27-32-11	D43261J	A17			D03683B	58			ALL
3733Z				LW	0-0	27-32-11	D43261J	DED			D03683B	DED			ALL
FRAA					0-0	23-34-01	D40173J	A08			D40173J			AA	YL951-YN260
FRAB					0-0	23-34-01	D40173J	B08			D40173J			AB	YL951-YN260
FRAC					0-0	23-34-01	D40173J	A18			D40173J			AC	YL951-YN260

WIRE LIST

D280A108

91-21-11

Section W0320

Page 37

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0321	286A0321			E3-2 SHELF (continued)											
FRAD					0-0	23-34-01	D40173J	B18			D40173J			AD	YL951-YN260
FRAE					0-0	23-34-01	D10461	55			D10461			AE	YL951-YL952
FRAE					0-0	23-34-01	D10461			AE	D10461	55			YL953-YN260

For training purposes only!

WIRE LIST

D280A108

91-21-11

Section W0320

Page 38 End

Dec 19/2011



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0330	286A0330				E3-3 SHELF (ZONE TEMP CONTROL) NB2											
0301	24		G6		2-6	21-51-12		D41802J	A03			D03858B	D12			YC051-YL999, YR301-YR323, YR325-YR328
0302	24		G6		2-6	21-51-12		D41802J	A02			D03858B	D13			YC051-YL999, YR301-YR323, YR325-YR328
0303	24		G6		2-2	21-51-12		D03858B	A06			TB3301Y	A041	1A		YC051-YL999, YR301-YR323, YR325-YR328
0304	24		G6		2-8	21-51-12		D41802J	A01			TB3301Y	A041	1A		YC051-YL999, YR301-YR323, YR325-YR328
0305	24		G6		2-3	21-51-12		D03860B	A09			TB3301Y	A041	1A		YC051-YL999, YR301-YR323, YR325-YR328
0306	24		G6		2-3	21-51-12		D41812J	A01			D03858B	C02			YC051-YL999, YR301-YR323, YR325-YR328
0307	24		G6		2-3	21-51-12		D41812J	A02			D03858B	D04			YC051-YL999, YR301-YR323, YR325-YR328
0308	24		G6		2-8	21-51-12		D41814J	A01			D03858A	C15			YC051-YL999, YR301-YR323, YR325-YR328
0309	24		G6		2-7	21-51-12		D41814J	B01			D03858B	D15			YC051-YL999, YR301-YR323, YR325-YR328
0310	24		G6		0-7	21-51-12		D03858B	C08			D03858B	C07			YC051-YL999, YR301-YR323, YR325-YR328
0311	24		G6		2-6	21-51-12		D03858B	B05			D03860B	C01			YC051-YL999, YR301-YR323, YR325-YR328
0312	24		G6		2-4	21-51-12		D41812J	A03			D03860B	A02			YC051-YL999, YR301-YR323, YR325-YR328
0313	22		G5		2-3	21-51-12		D03858B	C15			GD03303	AC..	1A		YC051-YL999, YR301-YR323, YR325-YR328

WIRE LIST
D280A108

91-21-11
Section W0330
Page 1
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W0330	286A0330				E3-3 SHELF (ZONE TEMP CONTROL) NB2 (continued)										
0314	24		G6		2-7	21-51-12	D03858B		D10		D41800J	A01		YC051-YL999, YR301-YR323, YR325-YR328	
0315	24		G6		2-7	21-51-12	D03858B		D09		D41800J	A02		YC051-YL999, YR301-YR323, YR325-YR328	
0316	22		G5		2-4	21-51-12	D03858A		D15		GD03303	DC..	1A	YC051-YL999, YR301-YR323, YR325-YR328	
0317	24		G6		2-9	21-51-12	D03858A		A06		D41800J	A03		YC051-YL999, YR301-YR323, YR325-YR328	
0318	24		G6		2-9	21-51-12	D03858A		B06		D41800J	A04		YC051-YL999, YR301-YR323, YR325-YR328	
0319	20		G5		2-1	21-51-12	D03858C		3		GD03303	ST..	1A	YC051-YL999, YR301-YR323, YR325-YR328	
0320	24		G6		2-8	21-51-12	D03858A		C09		D03860A	D06		YC051-YL999, YR301-YR323, YR325-YR328	
0321	24		G6		2-8	21-51-12	D03858A		B08		D03860A	A01		YC051-YL999, YR301-YR323, YR325-YR328	
0322	24		G6		2-8	21-51-13	D03858A		D10		D03860A	C13		YC051-YL999, YR301-YR323, YR325-YR328	
0323	24		G6		2-8	21-51-13	D03858A		D09		D03860A	C12		YC051-YL999, YR301-YR323, YR325-YR328	
0324	24		G6		2-8	21-51-13	D03858A		D07		D03860A	B09		YC051-YL999, YR301-YR323, YR325-YR328	
0325	24		G6		2-6	21-51-13	D03858B		C06		D03860B	A04		YC051-YL999, YR301-YR323, YR325-YR328	
0326	24		G6		2-6	21-51-13	D03858B		B03		D03860B	A05		YC051-YL999, YR301-YR323, YR325-YR328	

WIRE LIST

D280A108

91-21-11

Section W0330

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W0330	286A0330				E3-3 SHELF (ZONE TEMP CONTROL) NB2 (continued)											
0327	24		G6		3-2	21-51-13	D03860A		D11			D41800J	A07			YC051-YL999, YR301-YR323, YR325-YR328
0328	24		G6		3-2	21-51-13	D03860A		D12			D41800J	A08			YC051-YL999, YR301-YR323, YR325-YR328
0329	24		G6		3-2	21-51-13	D03860A		A15			D41800J	A09			YC051-YL999, YR301-YR323, YR325-YR328
0330	24		G6		3-2	21-51-13	D03860A		B15			D41800J	A10			YC051-YL999, YR301-YR323, YR325-YR328
0331	24		G6		2-6	21-51-14	D03858B		B15			D41802J	A04			YC051-YL999, YR301-YR323, YR325-YR328
0332	22		G5		2-3	21-51-14	D03858B		A15			GD03303	AC..	1A		YC051-YL999, YR301-YR323, YR325-YR328
0333	24		G6		2-6	21-51-14	D03858B		D08			D41802J	A05			YC051-YL999, YR301-YR323, YR325-YR328
0334	24		G6		2-6	21-51-14	D03858B		D06			D41802J	A06			YC051-YL999, YR301-YR323, YR325-YR328
0335	24		G6		2-6	21-51-14	D03858B		A13			D41802J	A07			YC051-YL999, YR301-YR323, YR325-YR328
0336	24		G6		2-6	21-51-14	D41802J		A08			D03858B	A12			YC051-YL999, YR301-YR323, YR325-YR328
0337	24		G6		2-9	21-51-14	D03858A		A13			D41800J	B01			YC051-YL999, YR301-YR323, YR325-YR328
0338	24		G6		2-9	21-51-14	D03858A		B13			D41800J	B02			YC051-YL999, YR301-YR323, YR325-YR328
0339	24		PK		2-6	21-51-22	D41808J		A02			D03860B	D13			YC051-YL999, YR301-YR323, YR325-YR328

WIRE LIST
D280A108

91-21-11
Section W0330
Page 3
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Description Fam FT-IN Diagram	From Equip Term Type Splice			To Equip Term Type Splice Effectivity					
W0330	286A0330			E3-3 SHELF (ZONE TEMP CONTROL) NB2 (continued)									
0340	24	PK		2-3	21-51-22	D03860B	A06		TB3301Y	B041	1A		YC051-YL999, YR301-YR323, YR325-YR328
0341	24	PK		2-2	21-51-22	D41808J	A01		TB3301Y	B041	1A		YC051-YL999, YR301-YR323, YR325-YR328
0342	24	G6		2-2	21-51-22	D03858B	A09		TB3301Y	B041	1A		YC051-YL999, YR301-YR323, YR325-YR328
0343	24	PK		2-6	21-51-22	D41826J	A01		D03860B	C02			YC051-YL999, YR301-YR323, YR325-YR328
0344	24	PK		2-6	21-51-22	D41826J	A02		D03860B	D04			YC051-YL999, YR301-YR323, YR325-YR328
0345	24	PK		2-8	21-51-22	D41822J	A01		D03860A	C15			YC051-YL999, YR301-YR323, YR325-YR328
0346	24	PK		2-7	21-51-22	D41822J	A02		D03860B	D15			YC051-YL999, YR301-YR323, YR325-YR328
0347	24	PK		2-6	21-51-22	D03860B	B05		D03858B	C01			YC051-YL999, YR301-YR323, YR325-YR328
0348	24	PK		2-1	21-51-22	D41826J	A03		D03858B	A02			YC051-YL999, YR301-YR323, YR325-YR328
0349	22	PA		2-2	21-51-22	D03860B	C15		GD03304	AC..	1A		YC051-YL999, YR301-YR323, YR325-YR328
0350	24	PK		2-3	21-51-22	D03860B	D10		D41806J	A01			YC051-YL999, YR301-YR323, YR325-YR328
0351	24	PK		2-3	21-51-22	D03860B	D09		D41806J	A02			YC051-YL999, YR301-YR323, YR325-YR328
0352	22	PA		2-4	21-51-22	D03860A	D15		GD03304	DC..	1A		YC051-YL999, YR301-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W0330

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0330	286A0330				E3-3 SHELF (ZONE TEMP CONTROL) NB2 (continued)											
0353	24		PK		2-4	21-51-22	D03860A	A06			D41806J	A03			YC051-YL999, YR301-YR323, YR325-YR328	
0354	24		PK		2-4	21-51-22	D03860A	B06			D41806J	A04			YC051-YL999, YR301-YR323, YR325-YR328	
0355	20		PA		2-1	21-51-22	D03860C	3			GD03304	ST..	1A		YC051-YL999, YR301-YR323, YR325-YR328	
0358	24		PK		2-8	21-51-22	D03860A	C09			D03858A	D06			YC051-YL999, YR301-YR323, YR325-YR328	
0359	24		PK		2-8	21-51-22	D03860A	B08			D03858A	A01			YC051-YL999, YR301-YR323, YR325-YR328	
0360	24		PK		2-8	21-51-23	D03860A	D10			D03858A	C13			YC051-YL999, YR301-YR323, YR325-YR328	
0361	24		PK		2-8	21-51-23	D03860A	D09			D03858A	C12			YC051-YL999, YR301-YR323, YR325-YR328	
0362	24		PK		2-8	21-51-23	D03860A	D07			D03858A	B09			YC051-YL999, YR301-YR323, YR325-YR328	
0363	24		PK		2-6	21-51-23	D03860B	C06			D03858B	A04			YC051-YL999, YR301-YR323, YR325-YR328	
0364	24		PK		2-6	21-51-23	D03860B	B03			D03858B	A05			YC051-YL999, YR301-YR323, YR325-YR328	
0365	24		PK		2-4	21-51-23	D03858A	D11			D41806J	A07			YC051-YL999, YR301-YR323, YR325-YR328	
0366	24		PK		2-4	21-51-23	D03858A	D12			D41806J	A08			YC051-YL999, YR301-YR323, YR325-YR328	
0367	24		PK		2-4	21-51-23	D03858A	A15			D41806J	A09			YC051-YL999, YR301-YR323, YR325-YR328	

WIRE LIST
D280A108

91-21-11
Section W0330
Page 5
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From			To			Effectivity		
Wire No.	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W0330	286A0330				E3-3 SHELF (ZONE TEMP CONTROL) NB2 (continued)										
0368	24		PK		2-4	21-51-23	D03858A		B15		D41806J	A10		YC051-YL999, YR301-YR323, YR325-YR328	
0369	24		PK		2-6	21-51-24	D03860B		B15		D41808J	A04		YC051-YL999, YR301-YR323, YR325-YR328	
0370	22		PA		2-2	21-51-24	D03860B		A15		GD03304	AC..	1A	YC051-YL999, YR301-YR323, YR325-YR328	
0371	24		PK		2-6	21-51-24	D03860B		D08		D41808J	A05		YC051-YL999, YR301-YR323, YR325-YR328	
0372	24		PK		2-6	21-51-24	D03860B		D06		D41808J	A06		YC051-YL999, YR301-YR323, YR325-YR328	
0373	24		PK		2-6	21-51-24	D03860B		A13		D41808J	A07		YC051-YL999, YR301-YR323, YR325-YR328	
0374	24		PK		2-6	21-51-24	D03860B		A12		D41808J	A08		YC051-YL999, YR301-YR323, YR325-YR328	
0375	24		PK		2-4	21-51-24	D03860A		A13		D41806J	B01		YC051-YL999, YR301-YR323, YR325-YR328	
0376	24		PK		2-4	21-51-24	D03860A		B13		D41806J	B02		YC051-YL999, YR301-YR323, YR325-YR328	
0377	24		PK		2-8	21-61-11	D41812J		B01		D41842J	A01		YC051-YL999, YR301-YR323, YR325-YR328	
0378	24		PK		2-8	21-61-11	D41802J		B02		TB3301Y	A045	1A	YC051-YL999, YR301-YR323, YR325-YR328	
0379	24		PK		2-2	21-61-11	D03858B		D01		TB3301Y	A045	1A	YC051-YL999, YR301-YR323, YR325-YR328	
0380	24		PK		2-11	21-61-11	D41802J		B05		D03860B	D02		YC051-YL999, YR301-YR323, YR325-YR328	

WIRE LIST

D280A108

91-21-11

Section W0330

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W0330	286A0330				E3-3 SHELF (ZONE TEMP CONTROL) NB2 (continued)											
0381	24		PK		2-11		21-61-11	D41802J		B04		D03860B		B12		YC051-YL999, YR301-YR323, YR325-YR328
0382	24		PK		2-11		21-61-11	D41802J		B03		D03860B		B13		YC051-YL999, YR301-YR323, YR325-YR328
0383	24		PK		2-8		21-61-11	D41802J		B01		TB3301Y		B045	1A	YC051-YL999, YR301-YR323, YR325-YR328
0384	24		PK		2-1		21-61-11	D41812J		A04		TB3301Y		B045	1A	YC051-YL999, YR301-YR323, YR325-YR328
0385	24		PK		2-3		21-61-11	D03860B		A10		TB3301Y		B045	1A	YC051-YL999, YR301-YR323, YR325-YR328
0386	24		PK		2-4		21-61-11	D41812J		A05		D03860B		A03		YC051-YL999, YR301-YR323, YR325-YR328
0392	24		PK		2-2		21-61-11	D03858B		B09		TB3301Y		A043	1A	YC051-YL999, YR301-YR323, YR325-YR328
0393	24		PK		2-2		21-61-11	D03858B		B10		TB3301Y		B043	1A	YC051-YL999, YR301-YR323, YR325-YR328
0394	24		PK		2-6		21-61-11	D03858B		C05		D03860B		B04		YC051-YL999, YR301-YR323, YR325-YR328
0395	24		PK		2-3		21-61-11	D03860B		B09		TB3301Y		A043	1A	YC051-YL999, YR301-YR323, YR325-YR328
0396	24		PK		2-3		21-61-11	D03860B		B10		TB3301Y		B043	1A	YC051-YL999, YR301-YR323, YR325-YR328
0397	24		PK		2-8		21-61-11	D41842J		A02		TB3301Y		A043	1A	YC051-YL999, YR301-YR323, YR325-YR328
0398	24		PK		2-8		21-61-11	D41842J		A03		TB3301Y		B043	1A	YC051-YL999, YR301-YR323, YR325-YR328

WIRE LIST
D280A108

91-21-11
Section W0330
Page 7
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type
W0330	286A0330				E3-3 SHELF (ZONE TEMP CONTROL) NB2 (continued)										
0399	24		PK		2-6	21-61-12	D41802J		B06		D03858B		B12		YC051-YL999, YR301-YR323, YR325-YR328
0400	24		PK		2-6	21-61-12	D41802J		B07		D03858B		B13		YC051-YL999, YR301-YR323, YR325-YR328
0401	24		PK		2-6	21-61-12	D41802J		B08		D03858B		D02		YC051-YL999, YR301-YR323, YR325-YR328
0402	24		PK		2-3	21-61-12	D41812J		B02		D03858B		A03		YC051-YL999, YR301-YR323, YR325-YR328
0404	24		PK		2-2	21-61-12	D03858B		A10		TB3301Y		B045	1A	YC051-YL999, YR301-YR323, YR325-YR328
0405	24		PK		2-6	21-61-12	D03858B		B04		D03860B		C05		YC051-YL999, YR301-YR323, YR325-YR328
0406	24		PK		2-4	21-61-13	D41822J		A03		TB3301Y		B047	1A	YC051-YL999, YR301-YR323, YR325-YR328
0407	24		PK		2-6	21-61-13	D41808J		B05		D03860B		C12		YC051-YL999, YR301-YR323, YR325-YR328
0408	24		PK		2-6	21-61-13	D41808J		B04		D03860B		C13		YC051-YL999, YR301-YR323, YR325-YR328
0409	24		PK		2-6	21-61-13	D41808J		B03		D03860B		B02		YC051-YL999, YR301-YR323, YR325-YR328
0410	24		PK		2-6	21-61-13	D41808J		B02		D03860B		D03		YC051-YL999, YR301-YR323, YR325-YR328
0411	24		PK		2-3	21-61-13	D03860B		A08		TB3301Y		A047	1A	YC051-YL999, YR301-YR323, YR325-YR328
0412	24		PK		2-2	21-61-13	D41808J		B01		TB3301Y		A047	1A	YC051-YL999, YR301-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W0330

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W0330	286A0330				E3-3 SHELF (ZONE TEMP CONTROL) NB2 (continued)											
0413	24		PK		2-3	21-61-13	D41826J	B01			TB3301Y	A047	1A		YC051-YL999, YR301-YR323, YR325-YR328	
0414	24		PK		2-2	21-61-13	D03858B	B08			TB3301Y	A047	1A		YC051-YL999, YR301-YR323, YR325-YR328	
0415	24		PK		2-1	21-61-13	D41826J	B05			D03858B	C04			YC051-YL999, YR301-YR323, YR325-YR328	
0416	24		PK		2-0	21-61-13	D41806J	B03			TB3301Y	B047	1A		YC051-YL999, YR301-YR323, YR325-YR328	
0417	24		PK		2-7	21-61-13	D41818J	A05			TB3301Y	B047	1A		YC051-YL999, YR301-YR323, YR325-YR328	
0418	24		PK		2-3	21-61-13	D03860B	C09			D41806J	B04			YC051-YL999, YR301-YR323, YR325-YR328	
0419	24		PK		2-3	21-61-13	D03860B	C10			D41806J	B05			YC051-YL999, YR301-YR323, YR325-YR328	
0420	24		PK		2-8	21-61-13	D03860A	D05			D03858A	A09			YC051-YL999, YR301-YR323, YR325-YR328	
0421	24		PK		2-6	21-61-14	D41822J	A04			TB3301Y	B049	1A		YC051-YL999, YR301-YR323, YR325-YR328	
0422	24		PK		2-0	21-61-14	D41808J	B10			D03858B	C12			YC051-YL999, YR301-YR323, YR325-YR328	
0423	24		PK		2-0	21-61-14	D41808J	B09			D03858B	C13			YC051-YL999, YR301-YR323, YR325-YR328	
0444	24		PK		2-0	21-61-14	D41808J	B08			D03858B	B02			YC051-YL999, YR301-YR323, YR325-YR328	
0445	24		PK		2-0	21-61-14	D41808J	B07			D03858B	D03			YC051-YL999, YR301-YR323, YR325-YR328	

WIRE LIST
D280A108

91-21-11
Section W0330
Page 9
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Description Fam	Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W0330	286A0330			E3-3 SHELF (ZONE TEMP CONTROL) NB2 (continued)										
0446	24	PK		2-4	21-61-14	D03858B	A08			TB3301Y	A049	1A		YC051-YL999, YR301-YR323, YR325-YR328
0447	24	PK		2-4	21-61-14	D41808J	B06			TB3301Y	A049	1A		YC051-YL999, YR301-YR323, YR325-YR328
0448	24	PK		2-2	21-61-14	D41812J	A11			TB3301Y	A049	1A		YC051-YL999, YR301-YR323, YR325-YR328
0449	24	PK		2-2	21-61-14	D03860B	B08			TB3301Y	A049	1A		YC051-YL999, YR301-YR323, YR325-YR328
0450	24	PK		2-4	21-61-14	D41812J	A15			D03860B	C04			YC051-YL999, YR301-YR323, YR325-YR328
0451	24	PK		2-1	21-61-14	D41806J	A11			TB3301Y	B049	1A		YC051-YL999, YR301-YR323, YR325-YR328
0452	24	PK		2-8	21-61-14	D41818J	B03			TB3301Y	B049	1A		YC051-YL999, YR301-YR323, YR325-YR328
0453	24	PK		2-2	21-61-14	D41806J	A12			D03858B	C09			YC051-YL999, YR301-YR323, YR325-YR328
0454	24	PK		2-2	21-61-14	D41806J	A13			D03858B	C10			YC051-YL999, YR301-YR323, YR325-YR328
0455	24	PK		2-8	21-61-14	D03858A	D05			D03860A	A09			YC051-YL999, YR301-YR323, YR325-YR328
0456	14	PA		2-1	21-25-11	D41824J	1			D41836J	3			YC051-YL999, YR301-YR323, YR325-YR328
0457	14	PA		2-1	21-25-11	D41824J	2			D41836J	2			YC051-YL999, YR301-YR323, YR325-YR328
0458	14	PA		2-1	21-25-11	D41824J	3			D41836J	1			YC051-YL999, YR301-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W0330

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W0330	286A0330				E3-3 SHELF (ZONE TEMP CONTROL) NB2 (continued)											
0461	24		PK		2-6	21-51-22	D41808J	A03			D03860B	D12			YC051-YL999, YR301-YR323, YR325-YR328	
0462	24		PK		2-3	21-61-11	D03860B	D01			TB3301Y	A045	1A		YC051-YL999, YR301-YR323, YR325-YR328	
0463	22		PA		2-10	21-61-15	D41802J	A09			TB3301Y	A051	1A		YC051-YL999, YR301-YR323, YR325-YR328	
0464	22		PA		2-5	21-61-15	D41826J	A09			TB3301Y	A051	1A		YC051-YL999, YR301-YR323, YR325-YR328	
0466	22		PA		2-2	21-61-15	D03860B	A07			TB3301Y	A051	1A		YC051-YL999, YR301-YR323, YR325-YR328	
0467	22		PA		2-4	21-61-15	D03858B	A07			TB3301Y	A051	1A		YC051-YL999, YR301-YR323, YR325-YR328	
2001B	24		Y2	GA	2-9	21-51-12	D03858A	B07			D41800J	A05			YC051-YL999, YR301-YR323, YR325-YR328	
2001R	24		Y2	GA	0-0	21-51-12	D03858A	A07			D41800J	A06			YC051-YL999, YR301-YR323, YR325-YR328	
2001Z				GA	0-0	21-51-12	D03858A	DED			D41800J	DED			YC051-YL999, YR301-YR323, YR325-YR328	
2002B	24		PL	GB	2-4	21-51-22	D03860A	A07			D41806J	A06			YC051-YL999, YR301-YR323, YR325-YR328	
2002R	24		PL	GB	0-0	21-51-22	D03860A	B07			D41806J	A05			YC051-YL999, YR301-YR323, YR325-YR328	
2003B	24		PL	GC	2-5	21-61-11	D41812J	A06			D03860A	C04			YC051-YL999, YR301-YR323, YR325-YR328	
2003R	24		PL	GC	0-0	21-61-11	D41812J	A07			D03860A	C05			YC051-YL999, YR301-YR323, YR325-YR328	

WIRE LIST
D280A108

91-21-11
Section W0330
Page 11
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0330	286A0330			E3-3 SHELF (ZONE TEMP CONTROL) NB2 (continued)											
2004B	24	PL	GD		3-1	21-61-11	D03860A	A05			D41814J	A03			YC051-YL999, YR301-YR323, YR325-YR328
2004R	24	PL	GD		0-0	21-61-11	D03860A	B05			D41814J	A02			YC051-YL999, YR301-YR323, YR325-YR328
2005B	24	PL	GE		2-4	21-61-12	D41812J	B06			D03858A	C04			YC051-YL999, YR301-YR323, YR325-YR328
2005R	24	PL	GE		0-0	21-61-12	D41812J	B07			D03858A	C05			YC051-YL999, YR301-YR323, YR325-YR328
2006B	24	PL	GF		2-8	21-61-12	D03858A	A05			D41814J	A05			YC051-YL999, YR301-YR323, YR325-YR328
2006R	24	PL	GF		0-0	21-61-12	D03858A	B05			D41814J	A04			YC051-YL999, YR301-YR323, YR325-YR328
2007B	24	PL	GG		2-6	21-61-13	D41818J	A09			D03858A	D13			YC051-YL999, YR301-YR323, YR325-YR328
2007R	24	PL	GG		0-0	21-61-13	D41818J	A08			D03858A	D14			YC051-YL999, YR301-YR323, YR325-YR328
2008B	24	PL	GH		2-11	21-61-13	D41818J	A07			D03860A	A04			YC051-YL999, YR301-YR323, YR325-YR328
2008R	24	PL	GH		0-0	21-61-13	D41818J	A06			D03860A	B04			YC051-YL999, YR301-YR323, YR325-YR328
2009B	24	PL	GI		2-11	21-61-13	D41818J	A03			D03860A	C06			YC051-YL999, YR301-YR323, YR325-YR328
2009R	24	PL	GI		0-0	21-61-13	D41818J	A04			D03860A	C07			YC051-YL999, YR301-YR323, YR325-YR328
2010B	24	PL	GJ		2-6	21-61-14	D03858A	A04			D41818J	B04			YC051-YL999, YR301-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W0330

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0330	286A0330				E3-3 SHELF (ZONE TEMP CONTROL) NB2 (continued)										
2010R	24	PL	GJ		0-0	21-61-14	D03858A	B04			D41818J	B05			YC051-YL999, YR301-YR323, YR325-YR328
2011B	24	PL	GK		2-6	21-61-14	D03858A	C06			D41818J	B01			YC051-YL999, YR301-YR323, YR325-YR328
2011R	24	PL	GK		0-0	21-61-14	D03858A	C07			D41818J	B02			YC051-YL999, YR301-YR323, YR325-YR328
2012B	24	PL	GL		2-11	21-61-14	D03860A	D13			D41818J	B07			YC051-YL999, YR301-YR323, YR325-YR328
2012R	24	PL	GL		0-0	21-61-14	D03860A	D14			D41818J	B06			YC051-YL999, YR301-YR323, YR325-YR328
3003B	24	PM	WC		2-5	21-61-11	D41812J	A10			D03860A	A02			YC051-YL999, YR301-YR323, YR325-YR328
3003R	24	PM	WC		0-0	21-61-11	D41812J	A09			D03860A	B02			YC051-YL999, YR301-YR323, YR325-YR328
3003Y	24	PM	WC		0-0	21-61-11	D41812J	A08			D03860A	C02			YC051-YL999, YR301-YR323, YR325-YR328
3004B	24	PM	WD		2-4	21-61-12	D41812J	B05			D03858A	A02			YC051-YL999, YR301-YR323, YR325-YR328
3004R	24	PM	WD		0-0	21-61-12	D41812J	B04			D03858A	B02			YC051-YL999, YR301-YR323, YR325-YR328
3004Y	24	PM	WD		0-0	21-61-12	D41812J	B03			D03858A	C02			YC051-YL999, YR301-YR323, YR325-YR328
3007B	24	PM	WG		2-2	21-61-13	D41826J	B07			D03858A	B11			YC051-YL999, YR301-YR323, YR325-YR328
3007R	24	PM	WG		0-0	21-61-13	D41826J	B08			D03858A	B12			YC051-YL999, YR301-YR323, YR325-YR328

WIRE LIST
D280A108

91-21-11
Section W0330
Page 13
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0330	286A0330			E3-3 SHELF (ZONE TEMP CONTROL) NB2 (continued)											
3007Y	24		PM	WG	0-0	21-61-13	D41826J	B06			D03858A	C11			YC051-YL999, YR301-YR323, YR325-YR328
3008B	24		PM	WH	2-7	21-61-13	D41826J	B04			D03860A	A03			YC051-YL999, YR301-YR323, YR325-YR328
3008R	24		PM	WH	0-0	21-61-13	D41826J	B03			D03860A	B03			YC051-YL999, YR301-YR323, YR325-YR328
3008Y	24		PM	WH	0-0	21-61-13	D41826J	B02			D03860A	C03			YC051-YL999, YR301-YR323, YR325-YR328
3009B	24		PM	WI	2-5	21-61-14	D41812J	A16			D03860A	C11			YC051-YL999, YR301-YR323, YR325-YR328
3009R	24		PM	WI	0-0	21-61-14	D41812J	A17			D03860A	B11			YC051-YL999, YR301-YR323, YR325-YR328
3009Y	24		PM	WI	0-0	21-61-14	D41812J	A18			D03860A	B12			YC051-YL999, YR301-YR323, YR325-YR328
3010B	24		PM	WJ	2-4	21-61-14	D41812J	A12			D03858A	C03			YC051-YL999, YR301-YR323, YR325-YR328
3010R	24		PM	WJ	0-0	21-61-14	D41812J	A13			D03858A	B03			YC051-YL999, YR301-YR323, YR325-YR328
3010Y	24		PM	WJ	0-0	21-61-14	D41812J	A14			D03858A	A03			YC051-YL999, YR301-YR323, YR325-YR328
W0331	286A0331			E3-3 SHELF BUNDLE											
0001	24		PK		2-11	23-27-16	D01967B	A02			M01997	1	1A		YC051-YD157
0002	24		PK		2-11	23-27-16	D01967B	B02			M01997	2	1A		YC051-YD157
0003	24		PK		2-11	23-27-16	D01967B	C02			M01997	3	1A		YC051-YD157
0004	24		PK		2-11	23-27-16	D01967B	D02			M01997	4	1A		YC051-YD157
0005	24		PK		2-11	23-27-16	D01967B	E02			M01997	5	1A		YC051-YD157
0006	24		PK		2-11	23-27-16	D01967B	F02			M01997	6	1A		YC051-YD157
0007	24		PK		2-11	23-27-16	D01967B	G02			M01997	7	1A		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0330

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0331	286A0331			E3-3 SHELF BUNDLE (continued)											
0008	24		PK		2-11	23-27-16	D01967B	H02			M01997	8	1A		YC051-YD157
0009	24		PK		2-11	23-27-16	D01967B	J02			M01997	9	1A		YC051-YD157
0010	24		PK		2-11	23-27-16	D01967B	K02			M01997	10	1A		YC051-YD157
0011	24		PK		2-11	23-27-16	D01967B	A03			M01997	11	1A		YC051-YD157
0012	24		PK		2-11	23-27-16	D01967B	B03			M01997	12	1A		YC051-YD157
0013	24		PK		2-11	23-27-16	D01967B	C03			M01997	13	1A		YC051-YD157
0014	24		PK		2-11	23-27-16	D01967B	D03			M01997	14	1A		YC051-YD157
0015	24		PK		2-11	23-27-16	D01967B	E03			M01997	15	1A		YC051-YD157
0016	24		PK		2-11	23-27-16	D01967B	F03			M01997	16	1A		YC051-YD157
0017	24		PK		2-11	23-27-16	D01967B	G03			M01997	17	1A		YC051-YD157
0018	24		PK		2-11	23-27-16	D01967B	H03			M01997	18	1A		YC051-YD157
0019	24		PK		2-11	23-27-16	D01967B	J03			M01997	19	1A		YC051-YD157
001CO				BZ	0-0	23-12-31	D43301J	= C1			D00539C	= C1			ALL
001CX			OF	BZ	1-10	23-12-31	D43301J	= A1			D00539C	1	DN		ALL
0020	24		PK		2-11	23-27-16	D01967B	K03			M01997	20	1A		YC051-YD157
0021	24		PK		2-11	23-27-16	D01967B	A04			M01997	21	1A		YC051-YD157
0022	24		PK		2-11	23-27-16	D01967B	B04			M01997	22	1A		YC051-YD157
0023	24		PK		2-11	23-27-16	D01967B	C04			M01997	23	1A		YC051-YD157
0024	24		PK		2-11	23-27-16	D01967B	D04			M01997	24	1A		YC051-YD157
0025	24		PK		2-1	23-27-16	M01997	25	1A		M01998	25	1A		YC051-YD157
0026	24		PK		2-8	23-27-16	D01967B	E04			M01998	1	1A		YC051-YD157
0027	24		PK		2-8	23-27-16	D01967B	F04			M01998	2	1A		YC051-YD157
0028	24		PK		2-8	23-27-16	D01967B	G04			M01998	3	1A		YC051-YD157
0029	24		PK		2-8	23-27-16	D01967B	H04			M01998	4	1A		YC051-YD157
0030	24		PK		2-8	23-27-16	D01967B	J04			M01998	5	1A		YC051-YD157
0031	24		PK		2-8	23-27-16	D01967B	K04			M01998	6	1A		YC051-YD157
0032	24		PK		2-8	23-27-16	D01967B	A05			M01998	7	1A		YC051-YD157
0033	24		PK		2-8	23-27-16	D01967B	B05			M01998	8	1A		YC051-YD157
0034	24		PK		2-8	23-27-16	D01967B	C05			M01998	9	1A		YC051-YD157
0035	24		PK		2-8	23-27-16	D01967B	D05			M01998	10	1A		YC051-YD157
0036	24		PK		2-8	23-27-16	D01967B	E05			M01998	11	1A		YC051-YD157
0037	24		PK		2-8	23-27-16	D01967B	F05			M01998	12	1A		YC051-YD157
0038	24		PK		2-8	23-27-16	D01967B	G05			M01998	13	1A		YC051-YD157
0039	24		PK		2-8	23-27-16	D01967B	H05			M01998	14	1A		YC051-YD157
0040	24		PK		2-8	23-27-16	D01967B	J05			M01998	15	1A		YC051-YD157
0041	24		PK		2-8	23-27-16	D01967B	K05			M01998	16	1A		YC051-YD157
0042	24		PK		2-8	23-27-16	D01967B	A06			M01998	17	1A		YC051-YD157
0043	24		PK		2-8	23-27-16	D01967B	B06			M01998	18	1A		YC051-YD157
0044	24		PK		2-3	23-27-16	M01998	26	1A		M01999	26	1A		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0330

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	Wire No.	GA	CO TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W0331	286A0331				E3-3 SHELF BUNDLE (continued)											
0045	24		PK		2-3	23-27-16	D01967B		C06			M01999	1	1A		YC051-YD157
0046	24		PK		2-3	23-27-16	D01967B		D06			M01999	2	1A		YC051-YD157
0047	24		PK		2-3	23-27-16	D01967B		E06			M01999	3	1A		YC051-YD157
0048	24		PK		2-3	23-27-16	D01967B		F06			M01999	4	1A		YC051-YD157
0049	24		PK		2-3	23-27-16	D01967B		G06			M01999	5	1A		YC051-YD157
0050	24		PK		2-3	23-27-16	D01967B		H06			M01999	6	1A		YC051-YD157
0051	24		PK		2-3	23-27-16	D01967B		J06			M01999	7	1A		YC051-YD157
0052	24		PK		2-3	23-27-16	D01967B		K06			M01999	8	1A		YC051-YD157
0053	24		PK		2-3	23-27-16	D01967B		A07			M01999	9	1A		YC051-YD157
0054	24		PK		2-3	23-27-16	D01967B		B07			M01999	10	1A		YC051-YD157
0055	24		PK		2-3	23-27-16	D01967B		C07			M01999	11	1A		YC051-YD157
0056	24		PK		2-3	23-27-16	D01967B		D07			M01999	12	1A		YC051-YD157
0057	24		PK		2-3	23-27-16	D01967B		E07			M01999	25	1A		YC051-YD157
0058	22		PA		1-11	23-27-11	D43309J		3			TB3301Y	B009	1A		YC051-YD157
0059	22		PA		2-0	23-27-11	D01967C		10			TB3301Y	B009	1A		YC051-YD157
0060	22		PA		2-2	23-27-11	D01967A		H09			TB3301Y	B009	1A		YC051-YD157
0061	20		PA		1-9	23-27-11	D01967C		7			GD03304	AC..	1A		YC051-YD157
0062	22		PA		2-1	23-27-11	D01967C		1			D43313J	6			YC051-YD157
0063	20		PA		1-8	23-27-11	D01967C		11			GD03303	DC..	1A		YC051-YD157
0064	20		PA		1-9	23-27-11	D01967C		8			GD03304	AC..	1A		YC051-YD157
0065	22		PA		2-6	23-27-11	D01967B		C09			D43315J	A01			YC051-YD157
0066	22		PA		2-6	23-27-11	D01967B		F09			D43315J	A02			YC051-YD157
0067	22		PA		1-9	23-27-11	D01967B		G09			GD03303	DC..	1A		YC051-YD157
0068	22		PA		2-7	23-27-11	D01967A		G09			D43315J	A03			YC051-YD157
0069	24		PK		3-0	23-27-11	D01967A		E06			D43321J	A14			YC051-YD157
0070	24		PK		1-11	23-27-11	D00539B		D11			GD03303	DC..	1A		YC051-YD157
0071	24		PK		2-6	23-27-11	D01967A		H05			D00539B	D07			YC051-YD157
0072	24		PK		2-6	23-27-11	D01967A		K07			D00539B	D08			YC051-YD157
0073	24		PK		2-6	23-27-11	D00539B		C07			D01967A	F07			YC051-YD157
0075	24		PK		1-10	23-27-11	D01967A		E07			GD03303	DC..	1A		YC051-YD157
0076	22		PA		1-10	23-27-12	D01967A		K15			GD03303	DC..	1A		YC051-YD157
0077	22		PA		3-1	23-27-12	D01967A		A15			D43307J	A12			YC051-YD157
0078	22		PA		3-1	23-27-12	D01967A		C15			D43307J	B12			YC051-YD157
0079	22		PA		3-1	23-27-12	D01967A		J15			D43307J	A13			YC051-YD157
0080	22		PA		3-1	23-27-12	D01967A		B15			D43307J	B13			YC051-YD157
0085	22		PA		2-5	23-27-13	D43313J		5			D43319J	A01			YC051-YD157
0088	22		PA		3-1	23-27-14	D01967A		H15			D43307J	A15			YC051-YD157
0089	22		PA		3-1	23-27-14	D01967A		G15			D43307J	B15			YC051-YD157
0094	24		PK		2-3	23-27-14	D01967A		D07			TB3301Z	A021	1A		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0330

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From			To					
Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W0331	286A0331			E3-3 SHELF BUNDLE (continued)											
0095	24	PK		2-3	23-27-14	D01967A	D11			TB3301Z	A021	1A		YC051-YD157	
0096	24	PK		2-3	23-27-14	D01967A	A14			TB3301Z	A021	1A		YC051-YD157	
0097	24	PK		2-3	23-27-14	D01967A	B14			TB3301Z	A021	1A		YC051-YD157	
0098	24	PK		2-3	23-27-14	D01967A	G14			TB3301Z	A021	1A		YC051-YD157	
0099	16	CQ		2-4	23-12-31	D43309J	4			TB3301V	B025	1		YC051-YD157	
0099	16	CQ		1-5	23-12-31	D43309J	4			SM00040		W		YD158-YN235, YR301-YR328	
0099	16	CQ		1-6	23-12-31	D43309J	4			SM00040		W		YN236-YN501	
0100	16	CQ		2-4	23-12-31	D43309J	7			TB3301V	B025	1		YC051-YD157	
0101	16	CQ		2-9	23-12-31	TB3301V	B025	1		D00539C	2			YC051-YD157	
0101	16	CQ		1-3	23-12-31	SM00040		W		D00539C	2			YD158-YR328	
0102	22	G5		2-2	23-12-31	D43315J	B01			D00539B	C01			YC051-YD157	
0102	22	G5		2-9	23-12-31	D43331J	B17			D00539B	C01			YD158-YL999	
0102	22	PA		2-9	23-12-31	D43331J	B17			D00539B	C01			YN231-YN235, YR301-YR328	
0102	22	PA		3-2	23-12-31	D43331J	B17			D00539B	C01			YN236-YN501	
0103	22	G5		2-2	23-12-31	D43315J	B02			D00539B	B14			YC051-YD157	
0103	22	PA		2-9	23-12-31	D43331J	B19			D00539B	B14			YD158-YN235, YR301-YR328	
0103	22	PA		3-2	23-12-31	D43331J	B19			D00539B	B14			YN236-YN501	
0104	16	CQ		2-8	23-12-31	D00539C	4			GD03305	DC..	1		YC051-YN235, YR301-YR328	
0104	16	CQ		2-9	23-12-31	D00539C	4			GD03305	DC..	1		YN236-YN501	
0105	22	G5		1-11	23-12-31	D00539B	D03			GD03303	DC..	1A		YC051-YN235, YR301-YR328	
0105	22	G5		2-0	23-12-31	D00539B	D03			GD03303	DC..	1A		YN236-YN501	
0106	22	G5		1-11	23-12-31	D00539B	A02			GD03303	DC..	1A		YC051-YN235, YR301-YR328	
0106	22	G5		2-0	23-12-31	D00539B	A02			GD03303	DC..	1A		YN236-YN501	
0107	22	G5		2-8	31-31-17	D43307J	A16			D00539B	D01			YC051-YD157	
0107	22	G5		2-8	31-31-17	D00539B	D01			D43307J	A16			YD158-YR328	
0135	18	CQ		1-6	23-12-31	D43329J	F			SM00040		W		YD158-YN235, YR301-YR328	
0135	18	CQ		1-7	23-12-31	D43329J	F			SM00040		W		YN236-YN501	
0139	20	PA		2-6	SPARE	D43307J	B16			D43315J	A09			YC051-YC053	
0140	20	PA		2-6	SPARE	D43307J	A17			D43315J	A10			YC051-YC053	
0147	22	G5		1-6	23-12-31	D43329J	B06			SM00039		W		YD158-YN235, YR301-YR328	
0147	22	G5		1-7	23-12-31	D43329J	B06			SM00039		W		YN236-YN501	

WIRE LIST

D280A108

91-21-11

Section W0330

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0331	286A0331			E3-3 SHELF BUNDLE (continued)											
0202	22		PA		2-7	23-27-31	D43313J		12		D43345J	B17			YD158-YN235, YR301-YR328
0202	22		PA		2-5	23-27-31	D43313J		12		D43345J	B17			YN236-YN501
0214	22		PA		2-0	23-27-38	D43307J		A12		D43347J	A01			YD158-YN235, YR301-YR328
0214	22		PA		2-4	23-27-38	D43307J		A12		D43347J	A01			YN236-YN501
0215	22		PA		2-0	23-27-38	D43307J		B13		D43347J	B01			YD158-YN235, YR301-YR328
0215	22		PA		2-4	23-27-38	D43307J		B13		D43347J	B01			YN236-YN501
0216	22		PA		2-0	23-27-38	D43307J		A13		D43347J	A02			YD158-YN235, YR301-YR328
0216	22		PA		2-4	23-27-38	D43307J		A13		D43347J	A02			YN236-YN501
0217	22		PA		2-0	23-27-38	D43307J		B12		D43347J	B02			YD158-YN235, YR301-YR328
0217	22		PA		2-4	23-27-38	D43307J		B12		D43347J	B02			YN236-YN501
0218	22		PA		2-0	23-27-38	D43307J		A15		D43347J	B03			YD158-YN235, YR301-YR328
0218	22		PA		2-4	23-27-38	D43307J		A15		D43347J	B03			YN236-YN501
0219	22		PA		2-0	23-27-38	D43307J		B15		D43347J	A03			YD158-YN235, YR301-YR328
0219	22		PA		2-4	23-27-38	D43307J		B15		D43347J	A03			YN236-YN501
0226	24		PK		2-0	23-27-39	D43321J		A14		D43345J	A17			YD158-YN235, YR301-YR328
0226	24		PK		2-4	23-27-39	D43321J		A14		D43345J	A17			YN236-YN501
0227	24		PK		1-6	23-11-16	D43329J		A06		SM00011		W		YD158-YD170
0228	22		PA		1-6	23-12-11	D43329J		A08		SM00020		W		YD158-YN235, YR301-YR328
0228	22		PA		1-7	23-12-11	D43329J		A08		SM00020		W		YN236-YN501
0231	24		PK		2-4	23-11-16	D43355J		A05		SM00011		W		YD158-YD170
0232	24		PK		2-3	23-11-16	D43363J		A05		SM00011		W		YD158-YD170
0233	24		PK		1-8	23-11-16	D43359J		A04		SM00011		W		YD158-YD170
0234	22		PA		3-4	23-11-11	D43359J		B04		D43363J	B05			YD158-YN235, YR301-YR328
0234	22		PA		3-5	23-11-11	D43359J		B04		D43363J	B05			YN236-YN501
0235	22		PA		3-4	23-11-11	D43359J		A05		D43363J	A06			YD158-YN235, YR301-YR328
0235	22		PA		3-5	23-11-11	D43359J		A05		D43363J	A06			YN236-YN501
0236	24		PK		1-8	23-12-41	D43359J		B05		SM00001		W		YD158-YR328
0237	24		PK		1-6	23-11-26	D43329J		B07		SM00013		W		YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0330

Page 18

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0331	286A0331				E3-3 SHELF BUNDLE (continued)										
0238	24		PK		2-3	23-11-26	D43363J	B06			SM00013		W		YD158-YD170
0239	24		PK		2-4	23-11-26	D43355J	B05			SM00013		W		YD158-YD170
0240	24		PK		1-5	23-11-26	D43361J	A02			SM00013		W		YD158-YD170
0241	22		PA		3-3	23-11-21	D43361J	B02			D43355J	A06			YD158-YN235, YR301-YR328
0241	22		PA		3-4	23-11-21	D43361J	B02			D43355J	A06			YN236-YN501
0242	22		PA		3-3	23-11-21	D43361J	A03			D43355J	B06			YD158-YN235, YR301-YR328
0242	22		PA		3-4	23-11-21	D43361J	A03			D43355J	B06			YN236-YN501
0243	24		G6		1-5	23-12-41	SM00012		W		D43361J	B03			YD158-YN235, YR301-YR328
0243	24		G6		1-6	23-12-41	SM00012		W		D43361J	B03			YN236-YN501
0245	24		PK		2-3	23-12-41	D43363J	A04			SM00001		W		YD158-YR328
0246	22		PA		2-3	23-12-11	D43363J	B04			SM00020		W		YD158-YR328
0247	24		PK		1-5	23-12-41	D43367J	A07			SM00001		W		YD158-YN235, YR301-YR328
0247	24		PK		1-6	23-12-41	D43367J	A07			SM00001		W		YN236-YN501
0248	22		PA		1-5	23-12-11	D43367J	B07			SM00020		W		YD158-YN235, YR301-YR328
0248	22		PA		1-6	23-12-11	D43367J	B07			SM00020		W		YN236-YN501
0249	22		PA		2-4	23-12-11	D43355J	A07			SM00020		W		YD158-YN235, YR301-YR328
0249	22		PA		2-5	23-12-11	D43355J	A07			SM00020		W		YN236-YN501
0251	24		G6		2-4	23-12-41	D43355J	A04			SM00012		W		YD158-YN235, YR301-YR328
0251	24		G6		2-5	23-12-41	D43355J	A04			SM00012		W		YN236-YN501
0252	22		G5		2-4	23-12-21	D43355J	B04			SM00021		W		YD158-YN235, YR301-YR328
0252	22		G5		2-5	23-12-21	D43355J	B04			SM00021		W		YN236-YN501
0253	24		G6		1-5	23-12-41	D43367J	A08			SM00012		W		YD158
0253	24		G6		1-8	23-12-41	D43314J	A07			SM00012		W		YL951-YN235, YR301-YR328
0253	24		G6		1-7	23-12-41	D43314J	A07			SM00012		W		YN236-YN501
0254	22		G5		1-5	23-12-21	D43367J	B08			SM00021		W		YD158
0254	22		G5		1-8	23-12-21	D43314J	B07			SM00021		W		YL951-YN235, YR301-YR328
0254	22		G5		1-7	23-12-21	D43314J	B07			SM00021		W		YN236-YN501
0255	22		G5		2-3	23-12-21	D43363J	B07			SM00021		W		YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0330

Page 19

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0331	286A0331				E3-3 SHELF BUNDLE (continued)										
0256	22		G5		1-6	23-12-21	D43329J	B08			SM00021		W		YD158-YN235, YR301-YR328
0256	22		G5		1-7	23-12-21	D43329J	B08			SM00021		W		YN236-YN501
0268	22		G5		1-5	23-12-31	D00539B	D05			SM00039		W		YD158-YR328
0269	22		G5		2-3	23-12-31	D43363J	A07			SM00039		W		YD158-YR328
0270	22		G5		2-4	23-12-31	D43355J	B07			SM00039		W		YD158-YN235, YR301-YR328
0270	22		G5		2-5	23-12-31	D43355J	B07			SM00039		W		YN236-YN501
0273	24		G6		1-5	23-12-31	D00539B	A09			SM00037		W		YD158-YR328
0274	24		G6		1-5	23-12-31	D00539B	B09			SM00037		W		YD158-YR328
0275	24		G6		1-5	23-12-31	D00539B	C09			SM00037		W		YD158-YR328
0339	20		PA		2-3	31-35-03	D02643C	4			GD03304	AC..	1A		YN236-YN501
0339	20		PA		1-9	31-35-03	D02643C	4			GD03304	AC..	1A		YR301-YR328
0340	22		PA		3-4	31-35-03	D02643C	1			D43049J	A01			YN236-YN501
0340	22		PA		2-4	31-35-03	D02643C	1			D43049J	A01			YR301-YR328
0341	22		PA		2-9	31-35-03	D02643A	K05			GD03303	DC..	1A		YN236-YN501
0341	22		PA		1-10	31-35-03	D02643A	K05			GD03303	DC..	1A		YR301-YR328
0342	24		PK		3-6	31-35-03	D02643A	D05			D43049J	A10			YN236-YN501
0342	24		PK		2-7	31-35-03	D02643A	D05			D43049J	A10			YR301-YR328
0344	24		PK		3-6	31-35-03	D02643A	G05			D43049J	B01			YN236-YN501
0344	24		PK		2-7	31-35-03	D02643A	G05			D43049J	B01			YR301-YR328
0345	22		PA		2-9	31-35-03	D02643A	A05			GD03303	DC..	1A		YN236-YN501
0345	22		PA		1-10	31-35-03	D02643A	A05			GD03303	DC..	1A		YR301-YR328
0346	24		PK		0-7	31-35-03	D02643A	G08			D02643A	D12			YN236-YR328
0347	24		PK		0-7	31-35-03	D02643A	A10			D02643A	G12			YN236-YR328
0355	22		PA		2-1	23-27-31	D43309J	3			D43379J	B01			YD158-YN235, YR301-YR328
0355	22		PA		2-3	23-27-31	D43309J	3			D43379J	B01			YN236-YN501
0470	22		G5		1-11	23-12-31	D00539B	C11			GD03303	DC..	1A		YD158-YN235, YR301-YR328
0470	22		G5		2-0	23-12-31	D00539B	C11			GD03303	DC..	1A		YN236-YN501
0484	20		G5		2-11	23-32-21	D43313J	3			D43321J	B14			YL951-YL967, YN231-YN235
0547	24		PK		3-6	31-35-03	D02643A	H07			D43049J	B02			YN236-YN501
0547	24		PK		2-7	31-35-03	D02643A	H07			D43049J	B02			YR301-YR328
0548	22		PA		2-9	31-35-03	D02643A	D10			GD03303	DC..	1A		YN236-YN501
0548	22		PA		1-10	31-35-03	D02643A	D10			GD03303	DC..	1A		YR301-YR328
0549	24		PK		3-6	31-35-03	D02643A	H06			D43049J	B03			YN236-YN501
0549	24		PK		2-7	31-35-03	D02643A	H06			D43049J	B03			YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W0330

Page 20

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0331	286A0331				E3-3 SHELF BUNDLE (continued)										
0551	24		PK		3-6	31-35-03	D02643A	J06			D43049J	B04			YN236-YN501
0551	24		PK		2-7	31-35-03	D02643A	J06			D43049J	B04			YR301-YR328
0553	22		PA		2-1	23-27-31	D43345J	A20			D43307J	A14			YL951-YL954, YN231-YN235
0554	22		PA		2-1	23-27-31	D43345J	B20			D43307J	B14			YL951-YL954, YN231-YN235
2034B	24		Y2	AG	2-0	23-27-39	D43345J	B04			D43321J	B17			YL951-YL954, YN231-YN235
2034R	24		Y2	AG	0-0	23-27-39	D43345J	A04			D43321J	A17			YL951-YL954, YN231-YN235
2034Z				AG	0-0	23-27-39	D43345J	PERG	1F		D43321J	PERG	1F		YL951-YL954, YN231-YN235
2061B	24		Y2	AJ	2-1	23-27-39	D43345J	B05			D43307J	B18			YL951-YL954, YN231-YN235
2061R	24		Y2	AJ	0-0	23-27-39	D43345J	A05			D43307J	A18			YL951-YL954, YN231-YN235
2061Z				AJ	0-0	23-27-39	D43345J	PERG	1F		D43307J	PERG	1F		YL951-YL954, YN231-YN235
2062B	24		Y2	AK	2-0	31-35-02	D43347J	B04			D43307J	B19			YN231-YN235
2062R	24		Y2	AK	0-0	31-35-02	D43347J	A04			D43307J	A19			YN231-YN235
2062Z				AK	0-0	31-35-02	D43347J	PERG	1F		D43307J	PERG	1F		YN231-YN235
2501B	24		Y2	AA	2-9	31-62-15	D01967A	CAP	Y		D43305J	B06			YC051-YD157
2501R	24		Y2	AA	0-0	31-62-15	D01967A	CAP	Y		D43305J	A06			YC051-YD157
2501Z				AA	0-0	31-62-15	D01967A	DED			D43305J	PERG	1F		YC051-YD157
2502B	24		Y2	AB	2-9	31-62-15	D01967A	CAP	Y		D43305J	B07			YC051-YD157
2502R	24		Y2	AB	0-0	31-62-15	D01967A	CAP	Y		D43305J	A07			YC051-YD157
2502Z				AB	0-0	31-62-15	D01967A	DED			D43305J	PERG	1F		YC051-YD157
2503B	24		Y2	AC	3-1	34-61-18	D01967A	E05			D43307J	B01			YC051-YC058
2503B	24		Y2	AC	3-1	31-32-15	D01967A	E05			D43307J	B01			YC059-YD157
2503R	24		Y2	AC	0-0	34-61-18	D01967A	D05			D43307J	A01			YC051-YC058
2503R	24		Y2	AC	0-0	31-32-15	D01967A	D05			D43307J	A01			YC059-YD157
2503Z				AC	0-0	34-61-18	D01967A	PERG	1A		D43307J	PERG	1F		YC051-YC058
2503Z				AC	0-0	31-32-15	D01967A	PERG	1A		D43307J	PERG	1F		YC059-YD157
2504B	24		Y2	AD	3-0	23-27-11	D01967A	G06			D43321J	B13			YC051-YD157
2504R	24		Y2	AD	0-0	23-27-11	D01967A	F06			D43321J	A13			YC051-YD157
2504Z				AD	0-0	23-27-11	D01967A	PERG	1A		D43321J	PERG	1F		YC051-YD157
2505B	24		M5	AE	2-4	23-27-11	D00539B	B13			TB3301Y	B005	1A		YC051-YD157
2505R	24		M5	AE	0-0	23-27-11	D00539B	A13			TB3301Y	A005	1A		YC051-YD157
2505ZI				AE	0-0	23-27-11	D00539B	PERG	1A		TB3301Y	A007	1A		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0330

Page 21

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice Effectivity
W0331	286A0331	E3-3 SHELF BUNDLE (continued)		
2505ZO		AE	0-0 23-27-11 GB03301 ST.. 1A	D00539B PERG 1A YC051-YD157
2506B	24 M5	AF	2-1 23-27-11 D01967A D09	TB3301Y B005 1A YC051-YD157
2506R	24 M5	AF	0-0 23-27-11 D01967A C09	TB3301Y A005 1A YC051-YD157
2506ZI		AF	0-0 23-27-11 D01967A DED	TB3301Y A007 1A YC051-YD157
2506ZO		AF	0-0 23-27-11 GB03301 ST.. 1A	D01967A PERG 1A YC051-YD157
2507B	24 M5	AY	2-5 23-22-11 D43315J B07	TB3301Y B005 1A YC051-YD157
2507B	24 M5	AE	2-2 23-22-11 D00539B B13	D43315J B07 YD158-YD170
2507B	24 M5	AE	2-9 23-22-11 D00539B B13	D43331J B15 YL951-YN235, YR301-YR328
2507B	24 M5	AE	3-2 23-22-11 D00539B B13	D43331J B15 YN236-YN501
2507R	24 M5	AY	0-0 23-22-11 D43315J A07	TB3301Y A005 1A YC051-YD157
2507R	24 M5	AE	0-0 23-22-11 D00539B A13	D43315J A07 YD158-YD170
2507R	24 M5	AE	0-0 23-22-11 D00539B A13	D43331J A15 YL951-YR328
2507ZI		AY	0-0 23-22-11 D43315J A06	TB3301Y A007 1A YC051-YD157
2507ZI		AE	0-0 23-22-11 D00539B DED	D43315J A06 YD158-YD170
2507ZI		AE	0-0 23-22-11 D00539B DED	D43331J A14 YL951-YR328
2507ZO		AY	0-0 23-22-11 D43315J PERG 1F	GB03301 ST.. 1A YC051-YD157
2507ZO		AE	0-0 23-22-11 D00539B PERG 1A	D43315J PERG 1F YD158-YD170
2507ZO		AE	0-0 23-22-11 D00539B PERG 1A	D43331J PERG 1F YL951-YR328
2508B	24 M5	AG	2-6 23-27-11 D01967A B09	D00539B B05 YC051-YD157
2508R	24 M5	AG	0-0 23-27-11 D01967A A09	D00539B A05 YC051-YD157
2508ZI		AG	0-0 23-27-11 D01967A PERG 1A	D00539B DED YC051-YD157
2508ZO		AG	0-0 23-27-11 D01967A PERG 1A	D00539B PERG 1A YC051-YD157
2509B	24 M5	AH	2-6 23-27-11 D01967A B07	D00539B B11 YC051-YD157
2509R	24 M5	AH	0-0 23-27-11 D01967A A07	D00539B A11 YC051-YD157
2509ZI		AH	0-0 23-27-11 D01967A PERG 1A	D00539B DED YC051-YD157
2509ZO		AH	0-0 23-27-11 D01967A PERG 1A	D00539B PERG 1A YC051-YD157
2510B	24 Y2	AI	3-0 23-27-14 D01967B K12	D43307J B08 YC051-YD157
2510R	24 Y2	AI	0-0 23-27-14 D01967B J12	D43307J A08 YC051-YD157
2510Z		AI	0-0 23-27-14 D01967B PERG 1A	D43307J PERG 1F YC051-YD157
2513B	24 Y2	AK	3-1 23-27-12 D43307J B04	TB3301Y B011 1A YC051-YD157
2513R	24 Y2	AK	0-0 23-27-12 D43307J A04	TB3301Y A011 1A YC051-YD157
2513Z		AK	0-0 23-27-12 D43307J PERG 1F	TB3301Y A009 1A YC051-YD157
2514B	24 Y2	AL	2-1 23-27-12 D01967B H15	TB3301Y B011 1A YC051-YD157
2514R	24 Y2	AL	0-0 23-27-12 D01967B G15	TB3301Y A011 1A YC051-YD157
2514Z		AL	0-0 23-27-12 D01967B PERG 1A	TB3301Y A009 1A YC051-YD157
2515B	24 Y2	AT	3-0 23-27-13 D43321J B06	TB3301Y B011 1A YC051-YD157
2515B	24 Y2	MP	3-3 23-11-26 TB3302Y B045 1A	D43361J B09 YD158-YD170
2515R	24 Y2	AT	0-0 23-27-13 D43321J A06	TB3301Y A011 1A YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0330

Page 22

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0331	286A0331			E3-3 SHELF BUNDLE (continued)											
2515R	24		Y2	MP	0-0	23-11-26	TB3302Y	A045	1A		D43361J	A09			YD158-YD170
2515Z				AT	0-0	23-27-13	D43321J	PERG	1F		TB3301Y	A009	1A		YC051-YD157
2515Z				MP	0-0	23-11-26	GB03302	ST..	1A		D43361J	PERG	1F		YD158-YD170
2516B	24		Y2	AM	3-0	31-35-02	D01967B	K07			D43307J	B06			YC051-YD157
2516R	24		Y2	AM	0-0	31-35-02	D01967B	J07			D43307J	A06			YC051-YD157
2516Z				AM	0-0	31-35-02	D01967B	PERG	1A		D43307J	PERG	1F		YC051-YD157
2517B	24		Y2	AN	2-9	31-35-02	D01967A	G01			D43305J	B05			YC051-YD157
2517R	24		Y2	AN	0-0	31-35-02	D01967A	F01			D43305J	A05			YC051-YD157
2517Z				AN	0-0	31-35-02	D01967A	PERG	1A		D43305J	PERG	1F		YC051-YD157
2518B	24		Y2	AO	2-5	23-27-13	D01967B	K14			D43319J	B02			YC051-YD157
2518R	24		Y2	AO	0-0	23-27-13	D01967B	J14			D43319J	A02			YC051-YD157
2518Z				AO	0-0	23-27-13	D01967B	PERG	1A		D43319J	PERG	1F		YC051-YD157
2519B	24		Y2	AP	2-6	23-27-13	D43319J	B03			TB3301Y	B013	1A		YC051-YD157
2519B	24		Y2	MT	2-7	23-27-37	D43333J	B09			TB3301Y	B013	1A		YD158-YN260
2519R	24		Y2	AP	0-0	23-27-13	D43319J	A03			TB3301Y	A013	1A		YC051-YD157
2519R	24		Y2	MT	0-0	23-27-37	D43333J	A09			TB3301Y	A013	1A		YD158-YN260
2519Z				AP	0-0	23-27-13	D43319J	PERG	1F		TB3301Y	A015	1A		YC051-YD157
2519Z				MT	0-0	23-27-37	D43333J	PERG	1F		GB03301	ST..	1A		YD158-YN260
2521B	24		Y2	MV	2-2	23-27-37	D43333J	B05			TB3301Y	B027	1A		YD158-YN235, YR301-YR328
2521B	24		Y2	MV	2-3	23-27-37	D43333J	B05			TB3301Y	B027	1A		YN236-YN501
2521R	24		Y2	MV	0-0	23-27-37	D43333J	A05			TB3301Y	A027	1A		YD158-YR328
2521Z				MV	0-0	23-27-37	D43333J	PERG	1F		GB03301	ST..	1A		YD158-YR328
2522B	24		Y2	AS	2-0	34-61-23	D01967B	B14			TB3301Y	B001	1A		YC051-YD157
2522R	24		Y2	AS	0-0	34-61-23	D01967B	A14			TB3301Y	A001	1A		YC051-YD157
2522Z				AS	0-0	34-61-23	D01967B	PERG	1A		GB03301	ST..	1A		YC051-YD157
2523B	24		Y2	AU	2-0	34-61-23	D01967B	D14			TB3301Y	B003	1A		YC051-YD157
2523R	24		Y2	AU	0-0	34-61-23	D01967B	C14			TB3301Y	A003	1A		YC051-YD157
2523Z				AU	0-0	34-61-23	D01967B	PERG	1A		GB03301	ST..	1A		YC051-YD157
2524B	24		Y2	BW	2-2	34-61-21	D01967B	K15			D43323J	B05			YC051-YD157
2524R	24		Y2	BW	0-0	34-61-21	D01967B	J15			D43323J	A05			YC051-YD157
2524Z				BW	0-0	34-61-21	D01967B	PERG	1A		D43323J	PERG	1F		YC051-YD157
2525B	24		Y2	AW	2-11	34-61-21	D01967B	H13			D43321J	B11			YC051-YD157
2525R	24		Y2	AW	0-0	34-61-21	D01967B	G13			D43321J	A11			YC051-YD157
2525Z				AW	0-0	34-61-21	D01967B	PERG	1A		D43321J	PERG	1F		YC051-YD157
2526B	24		Y2	AX	3-0	23-27-14	D43321J	B12			TB3301Y	B013	1A		YC051-YD157
2526R	24		Y2	AX	0-0	23-27-14	D43321J	A12			TB3301Y	A013	1A		YC051-YD157
2526Z				AX	0-0	23-27-14	D43321J	PERG	1F		TB3301Y	A015	1A		YC051-YD157
2527B	24		Y2	CA	2-0	23-27-14	D01967B	F15			TB3301Y	B013	1A		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0330

Page 23

Nov 12/2012

Bundle No. Wire No.	Part Number			Description Fam	FT-IN	Diagram	From				To				
	GA	CO	TY				Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0331	286A0331			E3-3 SHELF BUNDLE (continued)											
2527R	24	Y2	CA	0-0	23-27-14	D01967B	E15				TB3301Y	A013	1A		YC051-YD157
2527Z			CA	0-0	23-27-14	TB3301Y	A015	1A			D01967B	PERG	1A		YC051-YD157
2528B	24	Y2	AZ	3-0	23-27-14	TB3301Y	B013	1A			D43307J	B07			YC051-YD157
2528R	24	Y2	AZ	0-0	23-27-14	TB3301Y	A013	1A			D43307J	A07			YC051-YD157
2528Z			AZ	0-0	23-27-14	TB3301Y	A015	1A			D43307J	PERG	1F		YC051-YD157
2529B	24	M5	BX	2-2	23-12-31	D43315J	B04				D00539B	B01			YC051-YD157
2529B	24	M5	BX	2-9	23-12-31	D43331J	B16				D00539B	B01			YD158-YN235, YR301-YR328
2529B	24	M5	BX	3-2	23-12-31	D43331J	B16				D00539B	B01			YN236-YN501
2529R	24	M5	BX	0-0	23-12-31	D43315J	A04				D00539B	A01			YC051-YD157
2529R	24	M5	BX	0-0	23-12-31	D43331J	A16				D00539B	A01			YD158-YR328
2529ZI			BX	0-0	23-12-31	D43315J	B03				D00539B	DED			YC051-YD157
2529ZI			BX	0-0	23-12-31	D43331J	A17				D00539B	DED			YD158-YR328
2529ZO			BX	0-0	23-12-31	D43315J	PERG	1F			D00539B	PERG	1A		YC051-YD157
2529ZO			BX	0-0	23-12-31	D43331J	PERG	1F			D00539B	PERG	1A		YD158-YR328
2530B	24	M5	BV	2-2	23-12-31	D43315J	B05				D00539B	B15			YC051-YD157
2530B	24	M5	BV	2-9	23-12-31	D43331J	B18				D00539B	B15			YD158-YN235, YR301-YR328
2530B	24	M5	BV	3-2	23-12-31	D43331J	B18				D00539B	B15			YN236-YN501
2530R	24	M5	BV	0-0	23-12-31	D43315J	A05				D00539B	A15			YC051-YD157
2530R	24	M5	BV	0-0	23-12-31	D43331J	A18				D00539B	A15			YD158-YR328
2530ZI			BV	0-0	23-12-31	D43315J	B06				D00539B	DED			YC051-YD157
2530ZI			BV	0-0	23-12-31	D43331J	A19				D00539B	DED			YD158-YR328
2530ZO			BV	0-0	23-12-31	D43315J	PERG	1F			D00539B	PERG	1A		YC051-YD157
2530ZO			BV	0-0	23-12-31	D43331J	PERG	1F			D00539B	PERG	1A		YD158-YR328
2535B	24	Y2	CC	2-4	31-62-25	D01967A	CAP	Y			D43323J	B06			YC051-YD157
2535R	24	Y2	CC	0-0	31-62-25	D01967A	CAP	Y			D43323J	A06			YC051-YD157
2535Z			CC	0-0	31-62-25	D01967A	DED				D43323J	PERG	1F		YC051-YD157
2536B	24	Y2	CD	2-9	31-62-25	D01967A	CAP	Y			D43305J	B08			YC051-YD157
2536R	24	Y2	CD	0-0	31-62-25	D01967A	CAP	Y			D43305J	A08			YC051-YD157
2536Z			CD	0-0	31-62-25	D01967A	DED				D43305J	PERG	1F		YC051-YD157
2537B	24	Y2	CB	3-0	23-27-15	D01967B	F12				D43307J	B18			YC051-YD157
2537B	24	Y2	CA	2-1	23-27-34	D43345J	B04				D43307J	B18			YD158-YD170
2537R	24	Y2	CB	0-0	23-27-15	D01967B	E12				D43307J	A18			YC051-YD157
2537R	24	Y2	CA	0-0	23-27-34	D43345J	A04				D43307J	A18			YD158-YD170
2537Z			CB	0-0	23-27-15	D01967B	PERG	1A			D43307J	PERG	1F		YC051-YD157
2537Z			CA	0-0	23-27-34	D43345J	PERG	1F			D43307J	PERG	1F		YD158-YD170
2538B	22	X2	CE	3-0	23-32-21	D01967B	D12				D43307J	B19			YC051-YD157
2538R	22	X2	CE	0-0	23-32-21	D01967B	C12				D43307J	A19			YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0330

Page 24

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0331	286A0331				E3-3 SHELF BUNDLE (continued)										
2538Z				CE	0-0	23-32-21	D01967B	PERG	1A		D43307J	PERG	1F		YC051-YD157
2540B	24	Y2		CF	2-11	34-61-23	D43321J	B07			TB3301Y	B001	1A		YC051-YD157
2540R	24	Y2		CF	0-0	34-61-23	D43321J	A07			TB3301Y	A001	1A		YC051-YD157
2540Z				CF	0-0	34-61-23	D43321J	PERG	1F		GB03301	ST..	1A		YC051-YD157
2541B	24	Y2		CG	2-2	34-61-23	D43323J	B07			TB3301Y	B003	1A		YC051-YD157
2541B	24	Y2		CG	1-10	34-61-23	D43323J	B07			TB3301Y	B025	1A		YD158-YR328
2541R	24	Y2		CG	0-0	34-61-23	D43323J	A07			TB3301Y	A003	1A		YC051-YD157
2541R	24	Y2		CG	0-0	34-61-23	D43323J	A07			TB3301Y	A025	1A		YD158-YR328
2541Z				CG	0-0	34-61-23	D43323J	PERG	1F		GB03301	ST..	1A		ALL
2542B	24	Y2		CH	2-2	34-61-23	D43323J	B08			TB3301Y	B003	1A		YC051-YD157
2542B	24	Y2		CH	1-10	34-61-23	D43323J	B08			TB3301Y	B025	1A		YD158-YR328
2542R	24	Y2		CH	0-0	34-61-23	D43323J	A08			TB3301Y	A003	1A		YC051-YD157
2542R	24	Y2		CH	0-0	34-61-23	D43323J	A08			TB3301Y	A025	1A		YD158-YR328
2542Z				CH	0-0	34-61-23	D43323J	PERG	1F		GB03301	ST..	1A		ALL
2543B	24	Y2		CI	2-11	34-61-23	D43321J	B08			TB3301Y	B001	1A		YC051-YD157
2543R	24	Y2		CI	0-0	34-61-23	D43321J	A08			TB3301Y	A001	1A		YC051-YD157
2543Z				CI	0-0	34-61-23	D43321J	PERG	1F		GB03301	ST..	1A		YC051-YD157
2546B	24	Y2		NV	2-3	23-12-31	D43357J	B05			SM00036		W		YD158-YD170
2546B	24	Y2		NV	2-3	23-12-31	D43357J	B05			SM00029		W		YL951-YN235, YR301-YR328
2546B	24	Y2		NV	2-4	23-12-31	D43357J	B05			SM00029		W		YN236-YN501
2546R	24	Y2		NV	0-0	23-12-31	D43357J	A05			SM00035		W		YD158-YD170
2546R	24	Y2		NV	0-0	23-12-31	D43357J	A05			SM00028		W		YL951-YR328
2546Z				NV	0-0	23-12-31	D43357J	PERG	1F		SM00034		W		YD158-YD170
2546Z				NV	0-0	23-12-31	D43357J	PERG	1F		SM00030		W		YL951-YR328
2558B	24	Y2		PM	1-5	23-12-31	D00539B	D14			SM00036		W		YD158-YD170
2558B	24	Y2		PM	1-5	23-12-31	D00539B	D14			SM00029		W		YL951-YR328
2558R	24	Y2		PM	0-0	23-12-31	D00539B	C14			SM00035		W		YD158-YD170
2558R	24	Y2		PM	0-0	23-12-31	D00539B	C14			SM00028		W		YL951-YR328
2558Z				PM	0-0	23-12-31	D00539B	PERG	1A		SM00034		W		YD158-YD170
2558Z				PM	0-0	23-12-31	D00539B	PERG	1A		SM00030		W		YL951-YR328
2587B	24	Y2		PL	2-2	23-12-31	D43365J	B05			SM00036		W		YD158-YD170
2587B	24	Y2		PL	2-2	23-12-31	D43365J	B05			SM00029		W		YL951-YN235, YR301-YR328
2587B	24	Y2		PL	2-3	23-12-31	D43365J	B05			SM00029		W		YN236-YN501
2587R	24	Y2		PL	0-0	23-12-31	D43365J	A05			SM00035		W		YD158-YD170
2587R	24	Y2		PL	0-0	23-12-31	D43365J	A05			SM00028		W		YL951-YR328
2587Z				PL	0-0	23-12-31	D43365J	PERG	1F		SM00034		W		YD158-YD170
2587Z				PL	0-0	23-12-31	D43365J	PERG	1F		SM00030		W		YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0330

Page 25

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0331	286A0331			E3-3 SHELF BUNDLE (continued)											
2594B	22	X2	CV		3-0	23-27-15	D43321J	B16			D01967A	H07			YC051-YD157
2594R	22	X2	CV		0-0	23-27-15	D43321J	A16			D01967A	G07			YC051-YD157
2594Z			CV		0-0	23-27-15	D43321J	PERG	1F		D01967A	PERG	1A		YC051-YD157
2595B	24	Y2	BA		3-0	23-15-12	D43321J	B17			D01967A	D02			YC051-YD157
2595R	24	Y2	BA		0-0	23-15-12	D43321J	A17			D01967A	C02			YC051-YD157
2595Z			BA		0-0	23-15-12	D43321J	PERG	1F		D01967A	PERG	1A		YC051-YD157
2601B	24	Y2	AA		2-11	23-27-32	D43307J	B07			TB3301Y	B007	1A		YD158-YR328
2601R	24	Y2	AA		0-0	23-27-32	D43307J	A07			TB3301Y	A007	1A		YD158-YR328
2601Z			AA		0-0	23-27-32	D43307J	PERG	1F		GB03301	ST..	1A		YD158-YR328
2602B	24	Y2	AB		2-11	23-27-32	D43321J	B12			TB3301Y	B007	1A		YD158-YN235, YR301-YR328
2602B	24	Y2	AB		2-10	23-27-32	D43321J	B12			TB3301Y	B007	1A		YN236-YN501
2602R	24	Y2	AB		0-0	23-27-32	D43321J	A12			TB3301Y	A007	1A		YD158-YR328
2602Z			AB		0-0	23-27-32	D43321J	PERG	1F		GB03301	ST..	1A		YD158-YR328
2603B	24	Y2	AC		2-7	23-27-32	TB3301Y	B007	1A		D43345J	B08			YD158-YN235, YR301-YR328
2603B	24	Y2	AC		2-3	23-27-32	TB3301Y	B007	1A		D43345J	B08			YN236-YN501
2603R	24	Y2	AC		0-0	23-27-32	TB3301Y	A007	1A		D43345J	A08			YD158-YR328
2603Z			AC		0-0	23-27-32	GB03301	ST..	1A		D43345J	PERG	1F		YD158-YR328
2604B	24	Y2	AD		2-0	23-27-32	D43321J	B04			D43345J	B07			YD158-YN235
2604B	24	Y2	AD		2-4	23-27-32	D43321J	B04			D43345J	B07			YN236-YN260
2604R	24	Y2	AD		0-0	23-27-32	D43321J	A04			D43345J	A07			YD158-YN260
2604Z			AD		0-0	23-27-32	D43321J	PERG	1F		D43345J	PERG	1F		YD158-YN260
2605B	24	Y2	QE		2-1	23-27-33	D43319J	B02			D43345J	B03			YD158-YN235
2605B	24	Y2	QE		1-10	23-27-33	D43319J	B02			D43345J	B03			YN236-YN260
2605R	24	Y2	QE		0-0	23-27-33	D43319J	A02			D43345J	A03			YD158-YN260
2605Z			QE		0-0	23-27-33	D43319J	PERG	1F		D43345J	PERG	1F		YD158-YN260
2606B	24	Y2	AF		2-6	23-27-33	D43319J	B03			TB3301Y	B011	1A		YD158-YN260
2606R	24	Y2	AF		0-0	23-27-33	D43319J	A03			TB3301Y	A011	1A		YD158-YN260
2606Z			AF		0-0	23-27-33	D43319J	PERG	1F		GB03301	ST..	1A		YD158-YN260
2608B	24	Y2	AH		2-3	23-27-33	D43323J	B18			TB3301Y	B011	1A		YD158-YR328
2608R	24	Y2	AH		0-0	23-27-33	D43323J	A18			TB3301Y	A011	1A		YD158-YR328
2608Z			AH		0-0	23-27-33	D43323J	PERG	1F		GB03301	ST..	1A		YD158-YR328
2609B	24	Y2	AI		2-3	23-27-33	D43323J	B14			TB3301Y	B011	1A		YD158-YR328
2609R	24	Y2	AI		0-0	23-27-33	D43323J	A14			TB3301Y	A011	1A		YD158-YR328
2609Z			AI		0-0	23-27-33	D43323J	PERG	1F		GB03301	ST..	1A		YD158-YR328
2617B	24	Y2	AQ		1-11	23-27-36	D43359J	B07			D43345J	B18			YD158-YD170
2617R	24	Y2	AQ		0-0	23-27-36	D43359J	A07			D43345J	A18			YD158-YD170
2617Z			AQ		0-0	23-27-36	D43359J	PERG	1F		D43345J	PERG	1F		YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0330

Page 26

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From				To						
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0331	286A0331			E3-3 SHELF BUNDLE (continued)											
2618B	24	Y2	QS		1-11	23-27-36	D43359J	B06			D43345J	B19			YD158-YD170
2618R	24	Y2	QS		0-0	23-27-36	D43359J	A06			D43345J	A19			YD158-YD170
2618Z			QS		0-0	23-27-36	D43359J	PERG	1F		D43345J	PERG	1F		YD158-YD170
2621B	24	Y2	AU		3-5	23-27-37	D43306J	B05			TB3301Y	B027	1A		YD158-YN260
2621R	24	Y2	AU		0-0	23-27-37	D43306J	A05			TB3301Y	A027	1A		YD158-YN260
2621Z			AU		0-0	23-27-37	D43306J	PERG	1F		GB03301	ST..	1A		YD158-YN260
2624B	24	Y2	AX		3-5	23-27-37	D43306J	B02			TB3301Y	B027	1A		YD158-YR328
2624R	24	Y2	AX		0-0	23-27-37	D43306J	A02			TB3301Y	A027	1A		YD158-YR328
2624Z			AX		0-0	23-27-37	D43306J	PERG	1F		GB03301	ST..	1A		YD158-YR328
2625B	24	Y2	AY		2-1	23-27-37	TB3301Y	B013	1A		D43379J	B03			YD158-YN235
2625B	24	Y2	AY		2-2	23-27-37	TB3301Y	B013	1A		D43379J	B03			YN236-YN260
2625R	24	Y2	AY		0-0	23-27-37	TB3301Y	A013	1A		D43379J	A03			YD158-YN260
2625Z			AY		0-0	23-27-37	GB03301	ST..	1A		D43379J	PERG	1F		YD158-YN260
2626B	24	Y2	AZ		3-1	23-27-37	TB3301Y	B027	1A		D43345J	B13			YD158-YN235, YR301-YR328
2626B	24	Y2	AZ		2-10	23-27-37	TB3301Y	B027	1A		D43345J	B13			YN236-YN501
2626R	24	Y2	AZ		0-0	23-27-37	TB3301Y	A027	1A		D43345J	A13			YD158-YR328
2626Z			AZ		0-0	23-27-37	GB03301	ST..	1A		D43345J	PERG	1F		YD158-YR328
2629B	24	Y2	BC		2-3	23-27-38	D43305J	B06			D43347J	B11			YD158-YN235, YR301-YR328
2629B	24	Y2	BC		2-0	23-27-38	D43305J	B06			D43347J	B11			YN236-YN501
2629R	24	Y2	BC		0-0	23-27-38	D43305J	A06			D43347J	A11			YD158-YR328
2629Z			BC		0-0	23-27-38	D43305J	PERG	1F		D43347J	PERG	1F		YD158-YR328
2630B	24	Y2	BD		2-0	23-27-39	D43321J	B13			D43345J	B15			YD158-YN235, YR301-YR328
2630B	24	Y2	BD		2-4	23-27-39	D43321J	B13			D43345J	B15			YN236-YN501
2630R	24	Y2	BD		0-0	23-27-39	D43321J	A13			D43345J	A15			YD158-YR328
2630Z			BD		0-0	23-27-39	D43321J	PERG	1F		D43345J	PERG	1F		YD158-YR328
2632B	24	Y2	BF		2-3	31-62-15	D43305J	B07			D43347J	B10			YD158-YN235
2632B	24	Y2	BF		2-0	31-62-15	D43305J	B07			D43347J	B10			YN236-YN260
2632R	24	Y2	BF		0-0	31-62-15	D43305J	A07			D43347J	A10			YD158-YN260
2632Z			BF		0-0	31-62-15	D43305J	PERG	1F		D43347J	PERG	1F		YD158-YN260
2635B	24	Y2	BI		2-0	31-32-15	D43307J	B01			D43347J	B12			YD158-YN235, YR301-YR328
2635B	24	Y2	BI		2-4	31-32-15	D43307J	B01			D43347J	B12			YN236-YN501
2635R	24	Y2	BI		0-0	31-32-15	D43307J	A01			D43347J	A12			YD158-YR328
2635Z			BI		0-0	31-32-15	D43307J	PERG	1F		D43347J	PERG	1F		YD158-YR328
2637B	24	Y2	BK		1-5	34-61-21	D43323J	B05			D43379J	B16			YD158-YN235, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W0330

Page 27

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W0331	286A0331	E3-3 SHELF BUNDLE (continued)			
2637B	24 Y2 BK	1-7 34-61-21	D43323J B05	D43379J B16	YN236-YN501
2637R	24 Y2 BK	0-0 34-61-21	D43323J A05	D43379J A16	YD158-YR328
2637Z	24 Y2 BK	0-0 34-61-21	D43323J PERG 1F	D43379J PERG 1F	YD158-YR328
2638B	24 Y2 BL	1-11 34-61-21	D43321J B11	D43347J B17	YD158-YN235, YR301-YR328
2638B	24 Y2 BL	2-4 34-61-21	D43321J B11	D43347J B17	YN236-YN501
2638R	24 Y2 BL	0-0 34-61-21	D43321J A11	D43347J A17	YD158-YR328
2638Z	24 Y2 BL	0-0 34-61-21	D43321J PERG 1F	D43347J PERG 1F	YD158-YR328
2640B	24 Y2 BN	2-7 34-61-23	TB3301Y B015 1A	D43347J B13	YD158-YN235, YR301-YR328
2640B	24 Y2 BN	2-4 34-61-23	TB3301Y B015 1A	D43347J B13	YN236-YN501
2640R	24 Y2 BN	0-0 34-61-23	TB3301Y A015 1A	D43347J A13	YD158-YR328
2640Z	24 Y2 BN	0-0 34-61-23	GB03301 ST.. 1A	D43347J PERG 1F	YD158-YR328
2641B	24 Y2 BO	3-0 34-61-23	D43321J B07	TB3301Y B015 1A	YD158-YN235, YR301-YR328
2641B	24 Y2 BO	2-11 34-61-23	D43321J B07	TB3301Y B015 1A	YN236-YN501
2641R	24 Y2 BO	0-0 34-61-23	D43321J A07	TB3301Y A015 1A	YD158-YR328
2641Z	24 Y2 BO	0-0 34-61-23	D43321J PERG 1F	GB03301 ST.. 1A	YD158-YR328
2642B	24 Y2 BP	3-0 34-61-23	D43321J B08	TB3301Y B015 1A	YD158-YN235, YR301-YR328
2642B	24 Y2 BP	2-11 34-61-23	D43321J B08	TB3301Y B015 1A	YN236-YN501
2642R	24 Y2 BP	0-0 34-61-23	D43321J A08	TB3301Y A015 1A	YD158-YR328
2642Z	24 Y2 BP	0-0 34-61-23	D43321J PERG 1F	GB03301 ST.. 1A	YD158-YR328
2646B	24 Y2 BT	1-11 34-61-25	D43321J B01	D43347J B16	YD158-YN235
2646B	24 Y2 BT	2-4 34-61-25	D43321J B01	D43347J B16	YN236-YN260
2646R	24 Y2 BT	0-0 34-61-25	D43321J A01	D43347J A16	YD158-YN260
2646Z	24 Y2 BT	0-0 34-61-25	D43321J PERG 1F	D43347J PERG 1F	YD158-YN260
2647B	24 Y2 BU	1-11 34-61-25	D43321J B02	D43347J B15	YD158-YN235
2647B	24 Y2 BU	2-4 34-61-25	D43321J B02	D43347J B15	YN236-YN260
2647R	24 Y2 BU	0-0 34-61-25	D43321J A02	D43347J A15	YD158-YN260
2647Z	24 Y2 BU	0-0 34-61-25	D43321J PERG 1F	D43347J PERG 1F	YD158-YN260
2648B	24 Y2 RX	1-11 34-61-25	D43321J B03	D43347J B14	YD158-YN235
2648B	24 Y2 RX	2-4 34-61-25	D43321J B03	D43347J B14	YN236-YN260
2648R	24 Y2 RX	0-0 34-61-25	D43321J A03	D43347J A14	YD158-YN260
2648Z	24 Y2 RX	0-0 34-61-25	D43321J PERG 1F	D43347J PERG 1F	YD158-YN260
2649B	24 Y2 DQ	1-5 34-61-25	D43323J B01	D43379J B15	YD158-YN235
2649B	24 Y2 DQ	1-7 34-61-25	D43323J B01	D43379J B15	YN236-YN260
2649R	24 Y2 DQ	0-0 34-61-25	D43323J A01	D43379J A15	YD158-YN260
2649Z	24 Y2 DQ	0-0 34-61-25	D43323J PERG 1F	D43379J PERG 1F	YD158-YN260

WIRE LIST

D280A108

91-21-11

Section W0330

Page 28

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0331	286A0331			E3-3 SHELF BUNDLE (continued)											
2650B	24	Y2	DU		1-5	34-61-25	D43323J	B02			D43379J	B14			YD158-YN235
2650B	24	Y2	DU		1-7	34-61-25	D43323J	B02			D43379J	B14			YN236-YN260
2650R	24	Y2	DU		0-0	34-61-25	D43323J	A02			D43379J	A14			YD158-YN260
2650Z			DU		0-0	34-61-25	D43323J	PERG	1F		D43379J	PERG	1F		YD158-YN260
2651B	24	Y2	BY		1-5	34-61-25	D43323J	B03			D43379J	B13			YD158-YN235
2651B	24	Y2	BY		1-7	34-61-25	D43323J	B03			D43379J	B13			YN236-YN260
2651R	24	Y2	BY		0-0	34-61-25	D43323J	A03			D43379J	A13			YD158-YN260
2651Z			BY		0-0	34-61-25	D43323J	PERG	1F		D43379J	PERG	1F		YD158-YN260
2654B	24	Y2	CB		2-0	31-35-02	D43307J	B06			D43347J	B08			YD158-YN235, YR301-YR328
2654B	24	Y2	CB		2-4	31-35-02	D43307J	B06			D43347J	B08			YN236-YN501
2654R	24	Y2	CB		0-0	31-35-02	D43307J	A06			D43347J	A08			YD158-YR328
2654Z			CB		0-0	31-35-02	D43307J	PERG	1F		D43347J	PERG	1F		YD158-YR328
2655B	24	Y2	CC		2-3	31-35-02	D43305J	B05			D43347J	B07			YD158-YN235, YR301-YR328
2655B	24	Y2	CC		2-0	31-35-02	D43305J	B05			D43347J	B07			YN236-YN501
2655R	24	Y2	CC		0-0	31-35-02	D43305J	A05			D43347J	A07			YD158-YR328
2655Z			CC		0-0	31-35-02	D43305J	PERG	1F		D43347J	PERG	1F		YD158-YR328
2656B	24	Y2	CD		2-0	31-33-01	D43307J	B08			D43347J	B09			YD158-YN235, YR301-YR328
2656B	24	Y2	CD		2-4	31-33-01	D43307J	B08			D43347J	B09			YN236-YN501
2656R	24	Y2	CD		0-0	31-33-01	D43307J	A08			D43347J	A09			YD158-YR328
2656Z			CD		0-0	31-33-01	D43307J	PERG	1F		D43347J	PERG	1F		YD158-YR328
2657B	24	Y2	SG		1-7	23-11-11	D43391J	B02			SM00009		W		YD158-YR328
2657R	24	Y2	SG		0-0	23-11-11	D43391J	A02			SM00008		W		YD158-YR328
2657Z			SG		0-0	23-11-11	D43391J	PERG	1F		SM00010		W		YD158-YR328
2658B	24	Y2	SH		1-7	23-12-11	D43391J	B04			SM00018		W		YD158-YR328
2658R	24	Y2	SH		0-0	23-12-11	D43391J	A04			SM00017		W		YD158-YR328
2658Z			SH		0-0	23-12-11	D43391J	PERG	1F		SM00019		W		YD158-YR328
2659B	24	Y2	SI		1-6	23-12-41	D43329J	B04			SM00003		W		YD158-YN235, YR301-YR328
2659B	24	Y2	SI		1-7	23-12-41	D43329J	B04			SM00003		W		YN236-YN501
2659R	24	Y2	SI		0-0	23-12-41	D43329J	A04			SM00002		W		YD158-YR328
2659Z			SI		0-0	23-12-41	D43329J	PERG	1F		SM00004		W		YD158-YR328
2660B	24	Y2	CO		3-3	34-45-21	TB3302Y	B043	1A		D43347J	B18			YD158-YD170
2660B	24	Y2	CO		2-3	34-45-21	D43305J	B10			D43347J	B18			YL951-YN235, YR301-YR328
2660B	24	Y2	CO		2-0	34-45-21	D43305J	B10			D43347J	B18			YN236-YN501
2660R	24	Y2	CO		0-0	34-45-21	TB3302Y	A043	1A		D43347J	A18			YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0330

Page 29

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To				Effectivity	
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W0331	286A0331			E3-3 SHELF BUNDLE (continued)												
2660R	24	Y2	CO	0-0	34-45-21	D43305J	A10				D43347J	A18			YL951-YR328	
2660Z			CO	0-0	34-45-21	GB03302	ST..	1A			D43347J	PERG	1F		YD158-YD170	
2660Z			CO	0-0	34-45-21	D43305J	PERG	1F			D43347J	PERG	1F		YL951-YR328	
2662B	24	Y2	SL	3-3	34-45-21	TB3302Y	B043	1A			D43305J	B10			YD158-YD170	
2662R	24	Y2	SL	0-0	34-45-21	TB3302Y	A043	1A			D43305J	A10			YD158-YD170	
2662Z			SL	0-0	34-45-21	GB03302	ST..	1A			D43305J	PERG	1F		YD158-YD170	
2663B	24	Y2	CK	2-0	23-27-37	D43306J	B01				D43345J	B12			YD158-YN235, YR301-YR328	
2663B	24	Y2	CK	2-4	23-27-37	D43306J	B01				D43345J	B12			YN236-YN501	
2663R	24	Y2	CK	0-0	23-27-37	D43306J	A01				D43345J	A12			YD158-YR328	
2663Z			CK	0-0	23-27-37	D43306J	PERG	1F			D43345J	PERG	1F		YD158-YR328	
2666B	24	Y2	CN	1-10	23-27-37	D43333J	B06				D43379J	B09			YD158-YN235, YR301-YR328	
2666B	24	Y2	CN	2-0	23-27-37	D43333J	B06				D43379J	B09			YN236-YN501	
2666R	24	Y2	CN	0-0	23-27-37	D43333J	A06				D43379J	A09			YD158-YR328	
2666Z			CN	0-0	23-27-37	D43333J	PERG	1F			D43379J	PERG	1F		YD158-YR328	
2667B	24	Y2	SM	2-3	23-11-11	D43357J	B02				SM00009		W		YD158-YN235, YR301-YR328	
2667B	24	Y2	SM	2-4	23-11-11	D43357J	B02				SM00009		W		YN236-YN501	
2667R	24	Y2	SM	0-0	23-11-11	D43357J	A02				SM00008		W		YD158-YR328	
2667Z			SM	0-0	23-11-11	D43357J	PERG	1F			SM00010		W		YD158-YR328	
2668B	24	Y2	SS	2-2	23-11-11	D43365J	B02				SM00009		W		YD158-YN235, YR301-YR328	
2668B	24	Y2	SS	2-3	23-11-11	D43365J	B02				SM00009		W		YN236-YN501	
2668R	24	Y2	SS	0-0	23-11-11	D43365J	A02				SM00008		W		YD158-YR328	
2668Z			SS	0-0	23-11-11	D43365J	PERG	1F			SM00010		W		YD158-YR328	
2669B	24	Y2	ST	1-8	23-12-41	D43359J	B01				SM00003		W		YD158-YR328	
2669R	24	Y2	ST	0-0	23-12-41	D43359J	A01				SM00002		W		YD158-YR328	
2669Z			ST	0-0	23-12-41	D43359J	PERG	1F			SM00004		W		YD158-YR328	
2670B	24	Y2	SU	1-8	23-12-41	D43359J	B02				SM00006		W		YD158-YR328	
2670R	24	Y2	SU	0-0	23-12-41	D43359J	A02				SM00005		W		YD158-YR328	
2670Z			SU	0-0	23-12-41	D43359J	PERG	1F			SM00007		W		YD158-YR328	
2671B	24	Y2	SV	1-8	23-11-11	D43359J	B03				SM00009		W		YD158-YR328	
2671R	24	Y2	SV	0-0	23-11-11	D43359J	A03				SM00008		W		YD158-YR328	
2671Z			SV	0-0	23-11-11	D43359J	PERG	1F			SM00010		W		YD158-YR328	
2672B	24	Y2	SW	1-7	23-11-21	D43391J	B03				SM00015		W		YD158-YR328	
2672R	24	Y2	SW	0-0	23-11-21	D43391J	A03				SM00014		W		YD158-YR328	
2672Z			SW	0-0	23-11-21	D43391J	PERG	1F			SM00016		W		YD158-YR328	

WIRE LIST

D280A108

91-21-11

Section W0330

Page 30

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0331	286A0331				E3-3 SHELF BUNDLE (continued)										
2673B	24	Y2	SX		2-2	23-11-21	D43365J	B03			SM00015		W		YD158-YN235, YR301-YR328
2673B	24	Y2	SX		2-3	23-11-21	D43365J	B03			SM00015		W		YN236-YN501
2673R	24	Y2	SX		0-0	23-11-21	D43365J	A03			SM00014		W		YD158-YR328
2673Z			SX		0-0	23-11-21	D43365J	PERG	1F		SM00016		W		YD158-YR328
2674B	24	Y2	SY		2-3	23-11-21	D43357J	B03			SM00015		W		YD158-YN235, YR301-YR328
2674B	24	Y2	SY		2-4	23-11-21	D43357J	B03			SM00015		W		YN236-YN501
2674R	24	Y2	SY		0-0	23-11-21	D43357J	A03			SM00014		W		YD158-YR328
2674Z			SY		0-0	23-11-21	D43357J	PERG	1F		SM00016		W		YD158-YR328
2675B	24	Y2	SZ		1-5	23-11-21	D43361J	B01			SM00015		W		YD158-YN235, YR301-YR328
2675B	24	Y2	SZ		1-6	23-11-21	D43361J	B01			SM00015		W		YN236-YN501
2675R	24	Y2	SZ		0-0	23-11-21	D43361J	A01			SM00014		W		YD158-YR328
2675Z			SZ		0-0	23-11-21	D43361J	PERG	1F		SM00016		W		YD158-YR328
2676B	24	Y2	TA		2-3	23-12-41	D43363J	B01			SM00003		W		YD158-YR328
2676R	24	Y2	TA		0-0	23-12-41	D43363J	A01			SM00002		W		YD158-YR328
2676Z			TA		0-0	23-12-41	D43363J	PERG	1F		SM00004		W		YD158-YR328
2677B	24	Y2	TB		2-2	23-12-11	D43365J	B01			SM00018		W		YD158-YN235, YR301-YR328
2677B	24	Y2	TB		2-3	23-12-11	D43365J	B01			SM00018		W		YN236-YN501
2677R	24	Y2	TB		0-0	23-12-11	D43365J	A01			SM00017		W		YD158-YR328
2677Z			TB		0-0	23-12-11	D43365J	PERG	1F		SM00019		W		YD158-YR328
2678B	24	Y2	PC		1-5	23-12-41	D43367J	B01			SM00003		W		YD158-YN235, YR301-YR328
2678B	24	Y2	PC		1-6	23-12-41	D43367J	B01			SM00003		W		YN236-YN501
2678R	24	Y2	PC		0-0	23-12-41	D43367J	A01			SM00002		W		YD158-YR328
2678Z			PC		0-0	23-12-41	D43367J	PERG	1F		SM00004		W		YD158-YR328
2679B	24	Y2	PD		1-5	23-12-11	D43367J	B02			SM00018		W		YD158-YN235, YR301-YR328
2679B	24	Y2	PD		1-6	23-12-11	D43367J	B02			SM00018		W		YN236-YN501
2679R	24	Y2	PD		0-0	23-12-11	D43367J	A02			SM00017		W		YD158-YR328
2679Z			PD		0-0	23-12-11	D43367J	PERG	1F		SM00019		W		YD158-YR328
2680B	24	Y2	PE		1-5	23-12-41	D43367J	B03			SM00006		W		YD158-YN235, YR301-YR328
2680B	24	Y2	PE		1-6	23-12-41	D43367J	B03			SM00006		W		YN236-YN501
2680R	24	Y2	PE		0-0	23-12-41	D43367J	A03			SM00005		W		YD158-YR328
2680Z			PE		0-0	23-12-41	D43367J	PERG	1F		SM00007		W		YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0330

Page 31

Nov 12/2012



WIRE LIST

91-21-11

Section W0330

Page 32

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0331	286A0331			E3-3 SHELF BUNDLE (continued)											
2687B	24	Y2	TL		1-7	23-12-41	D43314J	B03			SM00003		W		YN236-YN501
2687R	24	Y2	TL		0-0	23-12-41	D43367J	A06			SM00002		W		YD158
2687R	24	Y2	TL		0-0	23-12-41	D43314J	A03			SM00002		W		YL951-YR328
2687Z			TL		0-0	23-12-41	D43367J	PERG	1F		SM00004		W		YD158
2687Z			TL		0-0	23-12-41	D43314J	PERG	1F		SM00004		W		YL951-YR328
2688B	24	Y2	TM		2-3	23-12-41	D43363J	B02			SM00006		W		YD158-YR328
2688R	24	Y2	TM		0-0	23-12-41	D43363J	A02			SM00005		W		YD158-YR328
2688Z			TM		0-0	23-12-41	D43363J	PERG	1F		SM00007		W		YD158-YR328
2689B	24	Y2	TN		2-2	23-12-21	D43365J	B04			SM00023		W		YD158-YN235, YR301-YR328
2689B	24	Y2	TN		2-3	23-12-21	D43365J	B04			SM00023		W		YN236-YN501
2689R	24	Y2	TN		0-0	23-12-21	D43365J	A04			SM00022		W		YD158-YR328
2689Z			TN		0-0	23-12-21	D43365J	PERG	1F		SM00024		W		YD158-YR328
2690B	24	Y2	TP		1-7	23-12-21	D43391J	B05			SM00023		W		YD158-YR328
2690R	24	Y2	TP		0-0	23-12-21	D43391J	A05			SM00022		W		YD158-YR328
2690Z			TP		0-0	23-12-21	D43391J	PERG	1F		SM00024		W		YD158-YR328
2691B	24	Y2	TQ		1-6	23-12-41	D43329J	B05			SM00006		W		YD158-YN235, YR301-YR328
2691B	24	Y2	TQ		1-7	23-12-41	D43329J	B05			SM00006		W		YN236-YN501
2691R	24	Y2	TQ		0-0	23-12-41	D43329J	A05			SM00005		W		YD158-YR328
2691Z			TQ		0-0	23-12-41	D43329J	PERG	1F		SM00007		W		YD158-YR328
2701B	24	Y2	UA		3-6	31-35-03	D02643A	E01			D43049J	B06			YN236-YN501
2701B	24	Y2	UA		2-7	31-35-03	D02643A	E01			D43049J	B06			YR301-YR328
2701R	24	Y2	UA		0-0	31-35-03	D02643A	K13			D43049J	B05			YN236-YR328
2701Z			UA		0-0	31-35-03	D02643A	PERG	1A		D43049J	PERG	1F		YN236-YR328
2703B	24	Y2	UC		3-6	23-11-16	TB3302Y	B043	1A		D43359J	B10			YD158-YD170
2703R	24	Y2	UC		0-0	23-11-16	TB3302Y	A043	1A		D43359J	A10			YD158-YD170
2703Z			UC		0-0	23-11-16	GB03302	ST..	1A		D43359J	PERG	1F		YD158-YD170
2707B	24	Y2	UG		1-6	23-12-41	D43329J	B03			SM00025		W		YD158-YN235, YR301-YR328
2707B	24	Y2	UG		1-7	23-12-41	D43329J	B03			SM00025		W		YN236-YN501
2707R	24	Y2	UG		0-0	23-12-41	D43329J	A03			SM00026		W		YD158-YR328
2707Z			UG		0-0	23-12-41	D43329J	PERG	1F		SM00027		W		YD158-YR328
2708B	24	Y2	UH		1-5	23-12-41	D00539B	B07			SM00025		W		YD158-YR328
2708R	24	Y2	UH		0-0	23-12-41	D00539B	A07			SM00026		W		YD158-YR328
2708Z			UH		0-0	23-12-41	D00539B	PERG	1A		SM00027		W		YD158-YR328
2709B	24	Y2	UI		1-7	23-12-31	D43391J	B01			SM00036		W		YD158-YD170
2709B	24	Y2	UI		1-7	23-12-31	D43391J	B01			SM00029		W		YL951-YR328
2709R	24	Y2	UI		0-0	23-12-31	D43391J	A01			SM00035		W		YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0330

Page 33

Nov 12/2012

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0331	286A0331			E3-3 SHELF BUNDLE (continued)											
2709R	24	Y2	UI		0-0	23-12-31	D43391J	A01			SM00028		W		YL951-YR328
2709Z			UI		0-0	23-12-31	D43391J	PERG	1F		SM00034		W		YD158-YD170
2709Z			UI		0-0	23-12-31	D43391J	PERG	1F		SM00030		W		YL951-YR328
2711B	24	Y2	UK		2-3	23-12-41	D43363J	B03			SM00025		W		YD158-YR328
2711R	24	Y2	UK		0-0	23-12-41	D43363J	A03			SM00026		W		YD158-YR328
2711Z			UK		0-0	23-12-41	D43363J	PERG	1F		SM00027		W		YD158-YR328
2714B	24	Y2	UN		2-4	23-12-41	D43355J	B03			SM00025		W		YD158-YN235, YR301-YR328
2714B	24	Y2	UN		2-5	23-12-41	D43355J	B03			SM00025		W		YN236-YN501
2714R	24	Y2	UN		0-0	23-12-41	D43355J	A03			SM00026		W		YD158-YR328
2714Z			UN		0-0	23-12-41	D43355J	PERG	1F		SM00027		W		YD158-YR328
2726B	24	Y2	VA		3-6	31-35-03	D02643A	K02			D43049J	A03			YN236-YN501
2726B	24	Y2	VA		2-7	31-35-03	D02643A	K02			D43049J	A03			YR301-YR328
2726R	24	Y2	VA		0-0	31-35-03	D02643A	K01			D43049J	A02			YN236-YR328
2726Z			VA		0-0	31-35-03	D02643A	PERG	1A		D43049J	PERG	1F		YN236-YR328
2727B	24	Y2	CV		3-6	31-35-03	D02643A	G02			D43049J	A05			YN236-YN501
2727B	24	Y2	CV		2-7	31-35-03	D02643A	G02			D43049J	A05			YR301-YR328
2727R	24	Y2	CV		0-0	31-35-03	D02643A	G01			D43049J	A04			YN236-YR328
2727Z			CV		0-0	31-35-03	D02643A	PERG	1A		D43049J	PERG	1F		YN236-YR328
2728B	24	Y2	CY		3-6	31-35-03	D02643A	D02			D43049J	A07			YN236-YN501
2728B	24	Y2	CY		2-7	31-35-03	D02643A	D02			D43049J	A07			YR301-YR328
2728R	24	Y2	CY		0-0	31-35-03	D02643A	D01			D43049J	A06			YN236-YR328
2728Z			CY		0-0	31-35-03	D02643A	PERG	1A		D43049J	PERG	1F		YN236-YR328
2729B	24	Y2	CX		3-6	31-35-03	D02643A	A02			D43049J	A09			YN236-YN501
2729B	24	Y2	CX		2-7	31-35-03	D02643A	A02			D43049J	A09			YR301-YR328
2729R	24	Y2	CX		0-0	31-35-03	D02643A	A01			D43049J	A08			YN236-YR328
2729Z			CX		0-0	31-35-03	D02643A	PERG	1A		D43049J	PERG	1F		YN236-YR328
2736B	24	Y2	VK		2-5	23-27-37	TB3301Y	B013	1A		D00539B	B12			YD158-YN235
2736B	24	Y2	VK		2-6	23-27-37	TB3301Y	B013	1A		D00539B	B12			YN236-YN260
2736B	24	Y2	VK		2-10	23-27-37	D43379J	B03			D00539B	B12			YN501
2736B	24	Y2	VK		2-8	23-27-37	D43379J	B03			D00539B	B12			YR301-YR328
2736R	24	Y2	VK		0-0	23-27-37	TB3301Y	A013	1A		D00539B	A12			YD158-YN260
2736R	24	Y2	VK		0-0	23-27-37	D43379J	A03			D00539B	A12			YN501-YR328
2736Z			VK		0-0	23-27-37	GB03301	ST..	1A		D00539B	PERG	1A		YD158-YN260
2736Z			VK		0-0	23-27-37	D43379J	PERG	1F		D00539B	PERG	1A		YN501-YR328
2738B	24	Y2	VM		2-8	23-27-37	D43379J	B08			D00539B	D10			YD158-YN235, YR301-YR328
2738B	24	Y2	VM		2-10	23-27-37	D43379J	B08			D00539B	D10			YN236-YN501
2738R	24	Y2	VM		0-0	23-27-37	D43379J	A08			D00539B	C10			YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0330

Page 34

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description		From	To								
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0331	286A0331			E3-3 SHELF BUNDLE (continued)											
2738Z				VM	0-0	23-27-37	D43379J	PERG	1F		D00539B	PERG	1A		YD158-YR328
2744B	24	Y2		VT	2-1	23-32-21	D43345J	B02			D43307J	B19			YD158-YD170
2744R	24	Y2		VT	0-0	23-32-21	D43345J	A02			D43307J	A19			YD158-YD170
2744Z				VT	0-0	23-32-21	D43345J	PERG	1F		D43307J	PERG	1F		YD158-YD170
2803B	24	Y2		SA	1-8	34-61-23	D43379J	B12			TB3301Y	B025	1A		YD158-YN235, YR301-YR328
2803B	24	Y2		SA	1-10	34-61-23	D43379J	B12			TB3301Y	B025	1A		YN236-YN501
2803R	24	Y2		SA	0-0	34-61-23	D43379J	A12			TB3301Y	A025	1A		YD158-YR328
2803Z				SA	0-0	34-61-23	D43379J	PERG	1F		GB03301	ST..	1A		YD158-YR328
2804B	24	Y2		SB	1-5	31-62-25	D43323J	B06			D43379J	B11			YD158-YN235
2804B	24	Y2		SB	1-7	31-62-25	D43323J	B06			D43379J	B11			YN236-YN260
2804R	24	Y2		SB	0-0	31-62-25	D43323J	A06			D43379J	A11			YD158-YN260
2804Z				SB	0-0	31-62-25	D43323J	PERG	1F		D43379J	PERG	1F		YD158-YN260
2805B	24	Y2		SE	2-4	23-27-34	D43321J	B09			D43345J	B01			YN501
2805B	24	Y2		SE	2-0	23-27-34	D43321J	B09			D43345J	B01			YR301-YR328
2805R	24	Y2		SE	0-0	23-27-34	D43321J	A09			D43345J	A01			YN501-YR328
2805Z				SE	0-0	23-27-34	D43321J	PERG	1F		D43345J	PERG	1F		YN501-YR328
2807B	24	Y2		SC	1-9	34-45-21	TB3302Y	B045	1A		D43379J	B17			YD158-YD170
2807B	24	Y2		SC	1-10	34-45-21	D43333J	B08			D43379J	B17			YL951-YN235, YR301-YR328
2807B	24	Y2		SC	2-0	34-45-21	D43333J	B08			D43379J	B17			YN236-YN501
2807R	24	Y2		SC	0-0	34-45-21	TB3302Y	A045	1A		D43379J	A17			YD158-YD170
2807R	24	Y2		SC	0-0	34-45-21	D43333J	A08			D43379J	A17			YL951-YR328
2807Z				SC	0-0	34-45-21	GB03302	ST..	1A		D43379J	PERG	1F		YD158-YD170
2807Z				SC	0-0	34-45-21	D43333J	PERG	1F		D43379J	PERG	1F		YL951-YR328
2808B	24	Y2		SD	1-10	34-45-21	TB3302Y	B045	1A		D43323J	B09			YD158-YD170
2808R	24	Y2		SD	0-0	34-45-21	TB3302Y	A045	1A		D43323J	A09			YD158-YD170
2808Z				SD	0-0	34-45-21	GB03302	ST..	1A		D43323J	PERG	1F		YD158-YD170
2810B	24	Y2		SJ	2-10	23-27-36	D43361J	B06			D43379J	B18			YD158-YD170
2810R	24	Y2		SJ	0-0	23-27-36	D43361J	A06			D43379J	A18			YD158-YD170
2810Z				SJ	0-0	23-27-36	D43361J	PERG	1F		D43379J	PERG	1F		YD158-YD170
2821B	24	Y2		SQ	1-5	23-27-33	D43323J	B15			D43379J	B19			YD158-YN235
2821B	24	Y2		SQ	1-7	23-27-33	D43323J	B15			D43379J	B19			YN236-YN260
2821R	24	Y2		SQ	0-0	23-27-33	D43323J	A15			D43379J	A19			YD158-YN260
2821Z				SQ	0-0	23-27-33	D43323J	PERG	1F		D43379J	PERG	1F		YD158-YN260
2822B	24	Y2		SR	2-1	23-27-33	D43379J	B20			TB3301Y	B011	1A		YD158-YN235, YR301-YR328
2822B	24	Y2		SR	2-2	23-27-33	D43379J	B20			TB3301Y	B011	1A		YN236-YN501
2822R	24	Y2		SR	0-0	23-27-33	D43379J	A20			TB3301Y	A011	1A		YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0330

Page 35

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0331		286A0331			E3-3 SHELF BUNDLE (continued)											
2822Z					SR	0-0	23-27-33	D43379J	PERG	1F		GB03301	ST..	1A		YD158-YR328
2837B		24		Y2	SD	2-4	23-27-34	D43321J		B18		D43345J	B09			YN501
2837B		24		Y2	SD	2-0	23-27-34	D43321J		B18		D43345J	B09			YR301-YR328
2837R		24		Y2	SD	0-0	23-27-34	D43321J		A18		D43345J	A09			YN501-YR328
2837Z					SD	0-0	23-27-34	D43321J	PERG	1F		D43345J	PERG	1F		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0330

Page 36 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0342	286A0342			FORWARD RIGHT HAND DOORWAY LINING											
0001	18	PA		1-10	35-21-31	D40042J		5			D12606	1			ALL
0002	18	PA		1-10	35-21-31	D40042J		6			D12606	2			ALL
0003	20	PA		3-0	33-51-12	D40042J		3			D02968	1			ALL
0004	20	PA		3-0	33-51-12	D40042J		4			D02968	2			ALL
2001B	22	PB	GA	3-11	23-31-04	D40042J		2			M01464	COM	Z		ALL
2001R	22	PB	GA	0-0	23-31-04	D40042J		1			M01464	1K	Z		YC051-YN260
2001R	22	PB	GA	0-0	23-31-04	D40042J		1			M01464	4K	Z		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0340

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I	W0352	286A0352			FORWARD LEFT HAND DOORWAY LINING											
I	0003	20		PA		2-4	33-51-12	D40040J		3		D02972		1		ALL
I	0004	20		PA		2-4	33-51-12	D40040J		4		D02972		2		ALL
I	0005	18		PA		2-4	35-21-21	D40040J		5		D11366		1		ALL
I	0006	18		PA		2-4	35-21-21	D40040J		6		D11366		2		ALL
I	2001B	22		PB	GA	3-4	23-31-04	D40040J		2		M00157	COM	Z		ALL
I	2001R	22		PB	GA	0-0	23-31-04	D40040J		1		M00157	1K	Z		YC051-YN260
I	2001R	22		PB	GA	0-0	23-31-04	D40040J		1		M00157	4K	Z		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0350

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To				
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0410	286A0410			E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2											
0001	20	PA		1-9	33-33-11	D40390J	B17				D43038J	A01			YC051-YC055
0001	20	PA		1-6	33-33-11	D40390J	B17				D43038J	A01			YC056-YR328
0002	20	PA		2-3	33-42-11	D40530J	B01				D43062J	A02			YC051-YC055
0002	20	PA		2-2	33-42-11	D40530J	B01				D43062J	A02			YC056-YR328
0003	20	PA		2-3	33-42-11	D40530J	A02				D43062J	A01			YC051-YC055
0003	20	PA		2-2	33-42-11	D40530J	A02				D43062J	A01			YC056-YR328
0004	20	PA		2-3	33-42-11	D40530J	A01				D43062J	F			YC051-YC055
0004	20	PA		2-2	33-42-11	D40530J	A01				D43062J	F			YC056-YR328
0005	22	CQ		3-4	23-51-51	D40390J	A03				TB4101X	A025	1A		YC051-YC055
0005	22	CQ		3-3	23-51-51	D40390J	A03				TB4101X	A025	1A		YC056-YR328
0006	22	CQ		3-4	23-51-51	D40390J	A10				TB4101X	A026	1A		YC051-YC055
0006	22	CQ		3-3	23-51-51	D40390J	A10				TB4101X	A026	1A		YC056-YR328
0007	22	CQ		3-2	23-51-51	D40378J	A01				TB4101X	A029	1A		YC051-YC055
0007	22	CQ		3-1	23-51-51	D40378J	A01				TB4101X	A029	1A		YC056-YR328
0008	22	CQ		3-4	23-51-51	D40378J	B10				TB4101Y	B023	1A		ALL
0009	22	PA		1-11	27-83-21	D40562J	A06				D40390J	A07			YC051-YC055
0009	22	PA		1-9	27-83-21	D40562J	A06				D40390J	A07			YC056-YR328
0010	22	PA		1-9	27-83-21	D40390J	A02				D43038J	B01			YC051-YC055
0010	22	PA		1-6	27-83-21	D40390J	A02				D43038J	B01			YC056-YR328
0011	24	G6		2-9	34-61-17	D44161J	A17				D00458B	17			YN231-YN501
0012	20	G5		2-5	34-61-17	D00458B	8				GD04103	DC..	1A		YN231-YN501
0013	24	G6		2-9	34-61-17	D44161J	A18				D00458B	7			YN231-YN501
0014	20	G5		2-0	34-61-17	D00458A	8				GD04104	DC..	1A		YN231-YN501
0015	22	G5		2-0	34-61-17	D44161J	A19				D43018J	B05			YC051-YC055
0015	22	G5		2-2	34-61-17	D44161J	A19				D43018J	B05			YC056-YR328
0016	24	GK		2-8	21-31-23	D41830J	B08				D10740B	B10			YC053, YC055
0016	24	GK		4-0	21-31-23	D41830J	B08				D10740B	B10			YC060-YC064
0016	24	PK		2-5	21-31-23	D41830J	A10				D10740B	B10			YC067-YD157
0017	24	GK		2-8	21-31-23	D41830J	B09				D10740B	D07			YC053, YC055
0017	24	GK		4-0	21-31-23	D41830J	B09				D10740B	D07			YC060-YC064
0017	24	PK		2-5	21-31-23	D41830J	A11				D10740B	D07			YC067-YD157
0018	20	GA		2-6	21-31-23	D41830J	B10				TB4101Y	A071	1A		YC053, YC055
0018	20	GA		4-0	21-31-23	D41830J	B10				TB4101Y	A071	1A		YC060-YC064
0018	20	PA		2-3	21-31-23	D41830J	A12				TB4101Y	A071	1A		YC067-YD157
0028	24	PK		2-3	29-32-11	D41010J	14				D43044J	A07			YC051-YC055
0028	24	PK		2-1	29-32-11	D41010J	14				D43044J	A07			YC056-YR328
0029	24	PK		2-3	29-32-11	D41010J	15				D43044J	B07			YC051-YC055
0029	24	PK		2-1	29-32-11	D41010J	15				D43044J	B07			YC056-YR328
0030	24	PK		2-1	29-33-11	D40530J	A10				D40390J	A01			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W0410

Page 1

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0410	286A0410				E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)											
0030	24		PK		1-11	29-33-11		D40530J	A10			D40390J	A01			YC056-YR328
0032	24		PK		2-1	49-52-31		D40904J	A01			TB4101Y	A061	1A		YC051-YC055
0032	24		PK		1-10	49-52-31		D40904J	A01			TB4101Y	A061	1A		YC056-YL999, YR301-YR328
0032	24		G6		1-10	49-52-31		D40904J	A01			TB4101Y	A061	1A		YN231-YN501
0033	24		PK		2-1	49-52-31		D40904J	B01			TB4101Y	B061	1A		YC051-YC055
0033	24		PK		1-10	49-52-31		D40904J	B01			TB4101Y	B061	1A		YC056-YL999, YR301-YR328
0033	24		G6		1-10	49-52-31		D40904J	B01			TB4101Y	B061	1A		YN231-YN501
0034	24		PK		2-3	49-52-31		D40904J	A02			TB4101Y	A069	1A		YC051-YC055
0034	24		PK		2-0	49-52-31		D40904J	A02			TB4101Y	A069	1A		YC056-YL999, YR301-YR328
0034	24		G6		2-0	49-52-31		D40904J	A02			TB4101Y	A069	1A		YN231-YN501
0035	24		PK		2-1	49-52-31		D40904J	B02			TB4101Y	B063	1A		YC051-YC055
0035	24		PK		1-10	49-52-31		D40904J	B02			TB4101Y	B063	1A		YC056-YL999, YR301-YR328
0035	24		G6		1-10	49-52-31		D40904J	B02			TB4101Y	B063	1A		YN231-YN501
0036	22		PA		2-1	49-52-31		D40904J	A03			TB4101Y	A063	1A		YC051-YC055
0036	22		PA		1-10	49-52-31		D40904J	A03			TB4101Y	A063	1A		YC056-YL999, YR301-YR328
0036	22		G5		1-10	49-52-31		D40904J	A03			TB4101Y	A063	1A		YN231-YN501
0037	24		PK		2-10	73-22-31		D40390J	B06			TB4101Y	A051	1A		YC051-YC055
0037	24		PK		2-9	73-22-31		D40390J	B06			TB4101Y	A051	1A		YC056-YR328
0038	24		PK		2-7	73-22-31		D40378J	B11			TB4101Y	A053	1A		ALL
0040	20		CQ		2-0	76-21-21		D40562J	A07			D40158J	A05			YC051-YC055
0040	20		CQ		1-9	76-21-21		D40562J	A07			D40158J	A05			YC056-YR328
0041	24		PK		1-11	80-11-11		D40158J	B04			TB4101Y	B069	1A		YC051-YC055
0041	24		PK		2-0	80-11-11		D40158J	B04			TB4101Y	B069	1A		YC056-YL999, YR301-YR328
0041	24		B6		2-0	80-11-11		D40158J	B04			TB4101Y	B069	1A		YN231-YN501
0042	20		PA		2-1	80-11-11		D40158J	A04			TB4101Y	B063	1A		YC051-YC055
0042	20		PA		2-2	80-11-11		D40158J	A04			TB4101Y	B063	1A		YC056-YL999, YR301-YR328
0042	20		CQ		2-2	80-11-11		D40158J	A04			TB4101Y	B063	1A		YN231-YN501
0043	24		B6		2-5	80-11-11		D40562J	B11			D41010J	11			YC051-YC055
0043	24		B6		2-2	80-11-11		D40562J	B11			D41010J	11			YC056-YR328
0044	20		PA		2-6	80-11-11		D40562J	A12			TB4101Y	B063	1A		YC051-YL999, YR301-YR328
0044	20		CQ		2-6	80-11-11		D40562J	A12			TB4101Y	B063	1A		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W0410

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0410	286A0410				E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)											
0045	24	B6			1-10	80-11-11		D41010J	12			TB4101Y	B069	1A		YC051-YC055
0045	24	B6			2-1	80-11-11		D41010J	12			TB4101Y	B069	1A		YC056-YR328
0046	14	PA			1-10	21-25-11		D40326J	1			D40330J	1			YC051-YC055
0046	14	PA			1-7	21-25-11		D40326J	1			D40330J	1			YC056-YR328
0047	14	PA			1-10	21-25-11		D40326J	2			D40330J	2			YC051-YC055
0047	14	PA			1-7	21-25-11		D40326J	2			D40330J	2			YC056-YR328
0048	14	PA			1-10	21-25-11		D40326J	3			D40330J	4			YC051-YC055
0048	14	PA			1-7	21-25-11		D40326J	3			D40330J	4			YC056-YR328
0049	22	PA			2-0	21-25-11		D40330J	3			TB4101Y	B053	1A		YN231-YN501
0050	22	PA			2-7	21-25-11		D00458B	2			TB4101Y	B053	1A		YN231-YN501
0051	22	PA			2-3	21-25-11		TB4101Y	B053	1A		D41010J	13			YN231-YN501
0052	22	PA			2-5	21-25-11		D00458B	1			TB4101Y	B071	1A		YN231-YN501
0053	22	PA			2-4	21-25-11		D40562J	A13			TB4101Y	B071	1A		ALL
0054	22	PA			2-6	21-25-11		D00458A	2			TB4101Y	B071	1A		YN231-YN501
0055	22	PA			2-8	21-25-11		D00458A	1			TB4101Y	B053	1A		YN231-YN501
0056	24	PK			2-6	21-31-23		D40390J	B08			D10740A	A13			YC051-YC055
0056	24	PK			2-4	21-31-23		D40390J	B08			D10740A	A13			YC056-YD157
0057	20	PA			2-4	21-31-23		D40390J	B09			TB4101Y	A071	1A		YC051-YC055
0057	20	PA			2-3	21-31-23		D40390J	B09			TB4101Y	A071	1A		YC056-YD157
0058	20	PA			1-10	21-31-23		D10740C	3			TB4101Y	A071	1A		YC051-YD157
0059	20	PA			1-6	21-31-23		D10740C	2			GD04104	DC..	1A		YC051-YD157
0060	20	PA			1-6	21-31-23		D10740C	4			GD04104	ST..	1A		YC051-YD157
0061	20	PA			2-1	21-31-23		D40066J	A01			TB4101Y	A071	1A		YC051-YD157
0062	24	PK			2-1	21-31-23		D40066J	A07			D10740B	B05			YC051-YC055
0062	24	PK			2-2	21-31-23		D40066J	A07			D10740B	B05			YC056-YD157
0063	22	GA			1-7	21-31-23		D10740B	B10			GD04104	DC..	1A		YC051-YC052, YC054, YC056-YC059, YC065
0064	22	PA			1-7	21-31-23		D10740B	C11			GD04104	DC..	1A		YC051-YD157
0065	22	PA			1-7	21-31-23		D10740B	C15			GD04104	DC..	1A		YC051-YD157
0066	24	PK			2-3	21-31-23		D40328J	B09			D10740A	A11			YC051-YC055
0066	24	PK			2-0	21-31-23		D40328J	B09			D10740A	A11			YC056-YD157
0067	24	PK			2-5	21-31-23		D40542J	B16			D10740B	B07			YC051-YC055
0067	24	PK			2-4	21-31-23		D40542J	B16			D10740B	B07			YC056-YD157
0068	24	PK			2-11	21-31-24		D40378J	B06			TB4101Z	A045	1A		YC051-YC055
0068	24	PK			2-10	21-31-24		D40378J	B06			TB4101Z	A045	1A		YC056-YD157
0069	24	PK			2-5	21-31-24		D10740B	B13			TB4101Z	A045	1A		YC051-YD157
0070	24	G6			2-5	21-31-24		D40378J	B01			D10740B	B01			YC051-YD157
0071	24	PK			2-5	21-31-24		D40378J	B02			D10740B	B04			YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0410

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0410	286A0410			E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)											
0072	24	PK		2-11	21-31-24	D40378J		B05			TB4101Z	A041	1A		YC051-YD157
0073	24	PK		2-5	21-31-24	D10740B		B12			TB4101Z	A041	1A		YC051-YD157
0074	24	PK		2-5	21-31-24	D40378J		B04			D10740B	B02			YC051-YD157
0075	24	PK		2-5	21-31-24	D40378J		B03			D10740B	B06			YC051-YD157
0076	24	PK		2-6	21-31-24	D40378J		A19			D10740A	D03			YC051-YD157
0077	24	PK		2-6	21-31-24	D40378J		A20			D10740A	A15			YC051-YD157
0078	24	PK		2-8	21-31-24	D10740B		B09			TB4101Y	B037	1A		YC051-YD157
0079	24	PK		3-1	21-31-24	D40378J		B07			TB4101Y	B037	1A		YC051-YD157
0080	24	PK		2-5	21-31-24	D41010J		23			TB4101Y	B037	1A		YC051-YC055
0080	24	PK		2-10	21-31-24	D41010J		23			TB4101Y	B037	1A		YC056-YD157
0081	24	PK		1-11	21-42-11	D40378J		A17			D43018J	A07			YC051-YC055
0081	24	PK		1-8	21-42-11	D40378J		A17			D43018J	A07			YC056-YR328
0082	24	PK		2-4	21-42-11	D40378J		A18			D43044J	B04			YC051-YC055
0082	24	PK		2-3	21-42-11	D40378J		A18			D43044J	B04			YC056-YR328
0088	24	G6		1-4	21-51-11	D40554J		A03			D43018J	A01			YC051-YC055
0088	24	G6		1-3	21-51-11	D40554J		A03			D43018J	A01			YC056-YR328
0089	24	G6		2-0	21-51-11	D40554J		B03			TB4101Y	A061	1A		YC051-YC055
0089	24	G6		2-1	21-51-11	D40554J		B03			TB4101Y	A061	1A		YC056-YR328
0090	24	G6		1-11	21-51-11	D43018J		A02			TB4101Y	A061	1A		YC051-YC055
0090	24	G6		2-1	21-51-11	D43018J		A02			TB4101Y	A061	1A		YC056-YR328
0091	24	B6		1-10	21-51-11	D40554J		B09			TB4101Y	A073	1A		YC051-YC055
0091	24	B6		2-0	21-51-11	D40554J		B09			TB4101Y	A073	1A		YC056-YR328
0092	24	B6		2-6	21-51-11	D00458B		4			TB4101Y	A073	1A		YN231-YN501
0093	24	B6		1-10	21-51-11	D40554J		A10			D00458B	5			YN231-YN501
0094	24	B6		1-10	21-51-11	D40554J		B10			D00458B	53			YN231-YN501
0095	24	B6		1-10	21-51-11	D43018J		A03			TB4101Y	A073	1A		YC051-YC055
0095	24	B6		1-11	21-51-11	D43018J		A03			TB4101Y	A073	1A		YC056-YR328
0096	24	B6		1-10	21-51-11	D40554J		A11			TB4101Y	B073	1A		YC051-YC055
0096	24	B6		2-0	21-51-11	D40554J		A09			TB4101Y	B073	1A		YC056-YR328
0097	24	B6		2-3	21-51-11	D43018J		A04			TB4101Z	A041	1A		YC051-YC055
0097	24	B6		2-5	21-51-11	D43018J		A04			TB4101Z	A041	1A		YC056-YR328
0098	24	B6		2-6	21-51-11	D00458B		35			TB4101Y	B073	1A		YN231-YN501
0099	24	PK		1-10	21-51-11	D40554J		A04			D00458A	6			YN231-YN501
0100	24	B6		1-10	21-51-11	D43018J		A06			TB4101Y	B073	1A		YC051-YC055
0100	24	B6		1-11	21-51-11	D43018J		A06			TB4101Y	B073	1A		YC056-YR328
0101	24	B6		2-7	21-51-11	D00458B		37			TB4101Y	B061	1A		YN231-YN501
0102	24	B6		1-11	21-51-11	D43018J		A05			TB4101Y	B061	1A		YC051-YC055
0102	24	B6		2-1	21-51-11	D43018J		A05			TB4101Y	B061	1A		YC056-YR328
0103	20	CQ		2-5	21-51-11	D00458B		10			GD04103	ST..	1A		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W0410

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From			To					
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0410	286A0410			E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)											
0104	24		PK		2-4	21-51-21	D43044J	A01			TB4101Y	A061	1A		YC051-YL999, YR301-YR328
0104	24		B6		2-4	21-51-21	D43044J	A01			TB4101Y	A061	1A		YN231-YN501
0105	24		PK		2-3	21-51-21	D40562J	A02			D43044J	B01			YC051-YC055
0105	24		PK		2-2	21-51-21	D40562J	A02			D43044J	B01			YC056-YL999, YR301-YR328
0105	24		B6		2-2	21-51-21	D40562J	A02			D43044J	B01			YN231-YN501
0106	24		PK		2-8	21-51-21	D43044J	A02			TB4101Z	A045	1A		YC051-YL999, YR301-YR328
0106	24		B6		2-8	21-51-21	D43044J	A02			TB4101Z	A045	1A		YN231-YN501
0107	24		B6		2-11	21-51-21	D00458A	18			TB4101Z	A045	1A		YN231-YN501
0108	24		B6		2-0	21-51-21	D40562J	B02			D00458A	5			YN231-YN501
0109	24		B6		2-0	21-51-21	D40562J	A03			D00458A	53			YN231-YN501
0110	24		PK		3-8	21-51-21	D40562J	B03			TB4102Y	A019	1A		YC051-YC055
0110	24		PK		3-10	21-51-21	D40562J	B03			TB4102Y	A019	1A		YC056-YL999, YR301-YR328
0110	24		B6		2-5	21-51-21	D40562J	B03			TB4101Y	A077	1A		YN231-YN501
0111	24		PK		3-8	21-51-21	D40562J	A04			TB4102Y	B019	1A		YC051-YC055
0111	24		PK		3-10	21-51-21	D40562J	A04			TB4102Y	B019	1A		YC056-YL999, YR301-YR328
0111	24		B6		2-5	21-51-21	D40562J	A04			TB4101Y	B077	1A		YN231-YN501
0112	24		B6		2-7	21-51-21	D00458A	35			TB4101Y	A077	1A		YN231-YN501
0113	24		B6		2-7	21-51-21	D00458A	4			TB4101Y	B077	1A		YN231-YN501
0114	24		B6		2-6	21-51-21	D00458A	37			TB4101Y	A069	1A		YN231-YN501
0115	24		PK		2-2	21-51-21	D43044J	B02			TB4101Y	A069	1A		YC051-YC055
0115	24		PK		2-3	21-51-21	D43044J	B02			TB4101Y	A069	1A		YC056-YL999, YR301-YR328
0115	24		B6		2-3	21-51-21	D43044J	B02			TB4101Y	A069	1A		YN231-YN501
0116	20		CQ		2-0	21-51-21	D00458A	10			GD04104	ST..	1A		YN231-YN501
0117	24		PK		3-6	21-51-21	D43044J	A03			TB4102Y	B019	1A		YC051-YC055
0117	24		PK		3-8	21-51-21	D43044J	A03			TB4102Y	B019	1A		YC056-YL999, YR301-YR328
0117	24		B6		2-4	21-51-21	D43044J	A03			TB4101Y	B077	1A		YN231-YN501
0118	24		PK		3-6	21-51-21	D43044J	B03			TB4102Y	A019	1A		YC051-YC055
0118	24		PK		3-8	21-51-21	D43044J	B03			TB4102Y	A019	1A		YC056-YL999, YR301-YR328
0118	24		B6		2-4	21-51-21	D43044J	B03			TB4101Y	A077	1A		YN231-YN501
0119	22		G5		2-0	21-51-14	D40378J	B09			D00458B	41			YN231-YN501
0120	24		G6		2-5	21-51-14	D40328J	A04			D00458B	15			YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W0410

Page 5

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W0410	286A0410				E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)											
0121	24		G6		2-9	21-51-14	D44161J	A07				D00458B	28		YN231-YN501	
0122	24		G6		2-0	21-51-14	D40378J	A11				D00458B	44		YN231-YN501	
0124	24		G6		2-6	21-51-14	D40244J	A01				D00458B	6		YN231-YN501	
0125	24		G6		2-6	21-51-14	D40244J	A02				D00458B	34		YN231-YN501	
0126	24		G6		2-6	21-51-14	D40244J	A03				D00458B	32		YN231-YN501	
0127	24		G6		2-7	21-51-14	D40534J	A04				D40244J	A04		YC051-YC055	
0127	24		G6		2-4	21-51-14	D40534J	A04				D40244J	A04		YC056-YR323, YR325-YR328	
0128	24		B6		2-0	21-51-15	D00458A	38				D40378J	A12		YN231-YN501	
0129	24		B6		1-10	21-51-15	D40554J	B07				D00458B	51		YN231-YN501	
0130	24		PK		1-10	21-51-15	D40554J	A07				D00458B	36		YN231-YN501	
0131	24		B6		2-6	21-51-15	D00458B	33				TB4101Y	A075	1A	YN231-YN501	
0132	24		B6		1-10	21-51-15	D43018J	A08				TB4101Y	A075	1A	YC051-YC055	
0132	24		B6		1-11	21-51-15	D43018J	A08				TB4101Y	A075	1A	YC056-YR328	
0133	24		B6		1-10	21-51-15	D43018J	A09				TB4101Y	A075	1A	YC051-YC055	
0133	24		B6		1-11	21-51-15	D43018J	A09				TB4101Y	A075	1A	YC056-YR328	
0134	24		G6		1-6	21-51-16	D40328J	A05				D40244J	B04		YN231-YN501	
0135	22		PA		1-7	21-51-24	D40390J	B07				D00458A	41		YN231-YN501	
0136	24		PK		1-7	21-51-24	D40390J	B20				D00458A	11		YN231-YN501	
0137	24		PK		1-9	21-51-24	D40542J	B08				D43038J	B03		YC051-YC055	
0137	24		PK		1-7	21-51-24	D40542J	B08				D43038J	B03		YC056-YR323, YR325-YR328	
0138	24		PK		1-7	21-51-24	D40390J	B04				D00458A	28		YN231-YN501	
0139	24		PK		1-7	21-51-24	D40390J	B05				D00458A	7		YN231-YN501	
0141	24		PK		1-9	21-51-24	D43038J	A02				D00458A	14		YN231-YN501	
0142	24		PK		1-9	21-51-24	D43038J	B02				D00458A	34		YN231-YN501	
0143	24		PK		1-9	21-51-24	D43038J	A03				D00458A	32		YN231-YN501	
0144	24		PK		2-0	21-51-25	D40562J	B13				D00458A	36		YN231-YN501	
0145	24		B6		2-0	21-51-25	D40562J	B04				D00458A	51		YN231-YN501	
0146	24		B6		2-6	21-51-25	TB4101Y	A067	1A			D00458A	33		YN231-YN501	
0147	24		PK		1-6	21-51-26	D40390J	A20				D43038J	A11		YN231-YN501	
0148	24		G6		2-6	21-61-21	D40244J	A05				D00458B	22		YN231-YN501	
0149	24		G6		2-6	21-61-21	D40244J	A06				D00458B	39		YN231-YN501	
0150	24		G6		2-0	21-61-21	D40378J	B17				D00458B	56		YN231-YN501	
0151	24		G6		1-11	21-61-21	D40534J	A15				D00458B	29		YN231-YN501	
0152	24		G6		2-5	21-61-21	D40534J	B18				TB4101Y	A055	1A	YN231-YN501	
0153	24		G6		2-5	21-61-21	D40534J	B15				TB4101Y	B055	1A	YN231-YN501	
0154	24		G6		2-7	21-61-21	D00458B	25				TB4101Y	A055	1A	YN231-YN501	
0155	24		G6		2-7	21-61-21	D00458B	47				TB4101Y	B055	1A	YN231-YN501	

WIRE LIST

D280A108

91-21-11

Section W0410

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W0410	286A0410				E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)											
0156	24		G6		2-6	21-61-21		D00454		17		TB4101Y	A055	1A		YN231-YN501
0157	24		G6		2-6	21-61-21		D00454		25		TB4101Y	B055	1A		YN231-YN501
0158	24		G6		1-10	21-61-21		D40534J		A16		D00454		20		YN231-YN501
0159	24		G6		1-10	21-61-21		D00454		19		D40534J		B16		YN231-YN501
0160	24		G6		1-10	21-61-21		D40534J		A17		D00454		10		YN231-YN501
0161	20		G5		2-4	21-61-21		D00454		32		GD04103	AC..	1A		YN231-YN501
0162	20		G5		2-4	21-61-21		D00454		9		GD04103	AC..	1A		YN231-YN501
0163	20		G5		2-4	21-61-21		D00454		1		GD04103	AC..	1A		YN231-YN501
0164	24		G6		2-4	21-61-21		D00454		21		D40328J		A06		YN231-YN501
0165	24		G6		2-4	21-61-21		D00454		22		D40328J		A07		YN231-YN501
0166	24		G6		2-4	21-61-21		D00454		14		D40328J		A08		YN231-YN501
0167	24		G6		2-4	21-61-21		D00454		15		D40328J		A09		YN231-YN501
0168	24		G6		1-11	21-61-21		D00454		16		D40378J		A10		YN231-YN501
0169	24		G6		1-10	21-61-21		D40534J		B17		D00454		23		YN231-YN501
0170	24		G6		1-10	21-61-21		D40534J		A18		D00454		24		YN231-YN501
0171	24		G6		2-4	21-61-21		D40534J		B19		D40244J		A07		YN231-YN501
0172	24		G6		2-4	21-61-21		D40534J		A20		D40244J		A08		YN231-YN501
0173	24		G6		1-11	21-61-21		D40534J		A19		D00458B		40		YN231-YN501
0174	24		PK		1-9	21-61-22		D43038J		A04		D00458A		13		YN231-YN501
0175	24		PK		1-9	21-61-22		D43038J		B04		D00458A		39		YN231-YN501
0176	24		PK		1-9	21-61-22		D43038J		A05		D00458A		56		YN231-YN501
0177	24		PK		1-8	21-61-22		D40542J		A09		D00458A		29		YN231-YN501
0178	24		PK		2-9	21-61-22		D40542J		B09		TB4101Y	A049	1A		YN231-YN501
0179	24		PK		2-9	21-61-22		D40542J		A10		TB4101Y	B049	1A		YN231-YN501
0180	24		PK		3-0	21-61-22		D00458A		16		TB4101Y	A049	1A		YN231-YN501
0181	24		PK		3-0	21-61-22		D00458A		17		TB4101Y	B049	1A		YN231-YN501
0182	24		PK		2-10	21-61-22		D00456		17		TB4101Y	A049	1A		YN231-YN501
0183	24		PK		2-10	21-61-22		D00456		25		TB4101Y	B049	1A		YN231-YN501
0184	24		PK		1-8	21-61-22		D40542J		B10		D00456		19		YN231-YN501
0185	24		PK		1-8	21-61-22		D40542J		A11		D00456		20		YN231-YN501
0186	24		PK		1-8	21-61-22		D40542J		B11		D00456		10		YN231-YN501
0187	24		PK		2-10	21-61-22		D00456		27		TB4101Y	B051	1A		YN231-YN501
0188	24		PK		2-10	21-61-22		D00456		28		TB4101Y	B051	1A		YN231-YN501
0189	24		PK		2-10	21-61-22		D00456		29		TB4101Y	B051	1A		YN231-YN501
0190	24		PK		1-9	21-61-22		D43038J		B05		D00456		21		YN231-YN501
0191	24		PK		1-9	21-61-22		D43038J		A06		D00456		22		YN231-YN501
0192	20		PA		1-11	21-61-22		D00456		32		GD04104	AC..	1A		YN231-YN501
0193	20		PA		1-11	21-61-22		D00456		9		GD04104	AC..	1A		YN231-YN501
0194	24		PK		1-9	21-61-22		D43038J		B06		D00456		14		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W0410

Page 7

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity			
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice	
W0410	286A0410				E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)											
0195	20		PA		1-11	21-61-22	D00456		1		GD04104	AC..	1A		YN231-YN501	
0196	24		PK		1-9	21-61-22	D43038J		A07		D00456	15			YN231-YN501	
0197	24		PK		1-9	21-61-22	D43038J		B07		D00456	16			YN231-YN501	
0198	24		PK		1-8	21-61-22	D40542J		B07		D00456	23			YN231-YN501	
0199	24		PK		1-8	21-61-22	D40542J		A08		D00456	24			YN231-YN501	
0200	24		PK		1-7	21-61-22	D40542J		A12		D43038J	A08			YN231-YN501	
0201	24		PK		1-7	21-61-22	D40542J		A17		D43038J	B08			YN231-YN501	
0202	24		PK		1-8	21-61-22	D40542J		B12		D00458A	40			YN231-YN501	
0206	20		G5		2-1	30-71-11	D43038J		B11		D40378J	B18			YC051-YC055	
0206	20		G5		2-0	30-71-11	D43038J		B11		D40378J	B18			YC056-YR328	
0207	24		PK		3-9	36-11-11	D40542J		A13		TB4102Y	A021	1A		YC051-YC055	
0207	24		PK		3-10	36-11-11	D40542J		A13		TB4102Y	A021	1A		YC056-YL999, YR301-YR328	
0207	24		PK		2-4	36-11-11	D40542J		A13		TB4101Y	A079	1A		YN231-YN501	
0208	24		PK		1-8	36-11-11	D40542J		B13		D00458A	49			YN231-YN501	
0209	24		PK		1-8	36-11-11	D40542J		A14		D00458A	48			YN231-YN501	
0210	24		G6		1-11	36-11-11	D40534J		B04		D00458B	48			YN231-YN501	
0211	24		G6		1-11	36-11-11	D40534J		A05		D00458B	49			YN231-YN501	
0212	24		G6		1-11	36-11-11	D40534J		B05		SM00001		W		ALL	
0213	24		PK		2-5	36-11-11	D40534J		A06		TB4101Y	A063	1A		ALL	
0214	24		PK		1-10	36-11-11	D40534J		B06		D43018J	B01			YC051-YC055	
0214	24		PK		1-7	36-11-11	D40534J		B06		D43018J	B01			YC056-YR328	
0215	24		PK		1-10	36-11-11	D40534J		A07		D43018J	B02			YC051-YC055	
0215	24		PK		1-7	36-11-11	D40534J		A07		D43018J	B02			YC056-YR328	
0216	24		PK		1-11	36-11-11	D40542J		B14		D43018J	B04			YC051-YC055	
0216	24		PK		1-7	36-11-11	D40542J		B14		D43018J	B04			YC056-YR328	
0217	24		PK		1-8	36-11-11	D40156J		A02		D00458A	50			YN231-YN501	
0218	24		PK		2-7	36-11-11	D00458A		45		TB4101Y	A079	1A		YN231-YN501	
0219	24		PK		3-10	36-11-11	D40156J		B01		TB4102Y	A021	1A		YC051-YC055	
0219	24		PK		3-11	36-11-11	D40156J		B01		TB4102Y	A021	1A		YC056-YL999, YR301-YR328	
0219	24		PK		2-5	36-11-11	D40156J		B01		TB4101Y	A079	1A		YN231-YN501	
0220	24		PK		1-8	36-11-11	D40156J		B02		D00458A	46			YN231-YN501	
0221	24		PK		2-6	36-11-11	D00458A		54		TB4101Y	B069	1A		YN231-YN501	
0222	24		G6		2-0	36-11-11	D40378J		A13		D00458B	54			YN231-YN501	
0223	24		G6		2-0	36-11-11	D40378J		A16		D00458B	46			YN231-YN501	
0224	24		G6		2-0	36-11-11	D40378J		A15		D00458B	50			YN231-YN501	
0225	24		G6		0-7	36-11-11	D00458B		45		SM00001		W		YN231-YN501	
0226	24		G6		2-1	36-11-11	D40378J		A14		SM00001		W		YC051-YC055	

WIRE LIST

D280A108

91-21-11

Section W0410

Page 8

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0410	286A0410				E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)										
0226	24		G6		2-0	36-11-11	D40378J	A14			SM00001		W		YC056-YR328
0227	24		PK		1-11	36-11-11	D43018J	B03			TB4101Y	A063	1A		YC051-YC055
0227	24		PK		2-1	36-11-11	D43018J	B03			TB4101Y	A063	1A		YC056-YR328
0228	24		PK		2-7	36-21-11	D41010J	4			D43038J	A09			YC051-YC055
0228	24		PK		2-3	36-21-11	D41010J	4			D43038J	A09			YC056-YR328
0229	24		PK		1-9	36-21-11	D40542J	A15			D43038J	B09			YC051-YC055
0229	24		PK		1-7	36-21-11	D40542J	A15			D43038J	B09			YC056-YL959, YN231-YN235
0229	24		PK		2-0	36-21-11	D40542J	A15			TB4101Y	B083	1A		YL963-YL999, YN236-YR328
0230	24		PK		1-9	36-21-11	D40542J	B15			D43038J	A10			YC051-YC055
0230	24		PK		1-7	36-21-11	D40542J	B15			D43038J	A10			YC056-YL959, YN231-YN235
0230	24		PK		2-0	36-21-11	D40542J	B15			TB4101Y	A083	1A		YL963-YL999, YN236-YR328
0232	22		CQ		3-0	34-24-15	D40554J	A01			TB4101X	B016	1A		YD158-YR328
0233	22		PA		2-3	23-22-11	D40328J	B06			TB4101X	B026	1A		YC051-YC055
0233	22		PA		2-5	23-22-11	D40328J	B06			TB4101X	B026	1A		YC056-YR328
0234	22		PA		2-3	23-22-11	D40328J	B07			TB4101X	A027	1A		YC051-YC055
0234	22		PA		2-5	23-22-11	D40328J	B07			TB4101X	A027	1A		YC056-YR328
0235	22		PA		2-3	23-22-11	D40328J	B08			TB4101X	A028	1A		YC051-YC055
0235	22		PA		2-5	23-22-11	D40328J	B08			TB4101X	A028	1A		YC056-YR328
0236	22		PA		2-0	23-71-01	D40328J	B04			TB4101X	A030	1A		YC051-YC055
0236	22		PA		2-2	23-71-01	D40328J	B04			TB4101X	A030	1A		YC056-YR328
0237	22		PA		2-0	23-71-01	D40328J	B05			TB4101X	B030	1A		YC051-YC055
0237	22		PA		2-2	23-71-01	D40328J	B05			TB4101X	B030	1A		YC056-YR328
0239	24		G6		1-10	34-61-17	D44161J	A09			TB4101Z	A041	1A		YC051-YC055
0239	24		G6		1-9	34-61-17	D44161J	A09			TB4101Z	A041	1A		YC056-YR328
0240	24		G6		1-10	34-61-17	D44161J	A10			TB4101Z	A045	1A		YC051-YC055
0240	24		G6		1-9	34-61-17	D44161J	A10			TB4101Z	A045	1A		YC056-YR328
0241	22		PA		2-8	22-14-11	D44161J	A15			TB4101X	A012	1A		YC051-YC055
0241	22		PA		2-7	22-14-11	D44161J	A15			TB4101X	A012	1A		YC056-YL999, YR301-YR328
0241	22		G5		2-7	22-14-11	D44161J	A15			TB4101X	A012	1A		YN231-YN501
0242	22		PA		2-0	21-51-15	D00458A	42			GD04104	DC..	1A		YN231-YN501
0243	24		PK		2-5	21-31-11	D40542J	A07			D10740B	B03			YC051-YC055
0243	24		PK		2-4	21-31-11	D40542J	A07			D10740B	B03			YC056-YD157
0244	24		B6		2-11	21-51-11	D00458B	43			TB4101Z	A041	1A		YN231-YN501
0246	20		PA		2-4	21-61-15	D40542J	A12			D43044J	B05			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W0410

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0410	286A0410			E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)											
0246	20		PA		2-1	21-61-15	D40542J	A12			D43044J	B05			YC056-YL999, YR301-YR328
0247	24		PK		2-0	29-34-11	D40562J	A14			D43062J	G			ALL
0252	24		B6		1-9	21-51-11	D44161J	B10			TB4101Z	A041	1A		YD158-YR328
0253	24		B6		2-8	21-51-21	D40390J	B14			TB4101Z	A045	1A		YD158-YR328
0254	22		PA		2-2	23-43-11	D40542J	A01			TB4101Y	A081	1A		YC051-YC055
0254	22		PA		2-0	23-43-11	D40542J	A01			TB4101Y	A081	1A		YC056-YD157
0255	22		PA		2-2	23-42-11	D40542J	A02			TB4101Y	A081	1A		YC051-YC055
0255	22		PA		2-0	23-42-11	D40542J	A02			TB4101Y	A081	1A		YC056-YD157
0258	20		CQ		2-5	47-30-11	D43018J	B09			TB4101Z	A041	1A		YL951-YR328
0264	22		G5		2-3	34-21-12	D44161J	B19			TB4101X	B027	1A		YL951-YR328
0265	22		PA		2-0	34-21-22	D44161J	B20			TB4101X	B029	1A		YL951-YR328
0266	20		PA		2-7	21-31-23	D41830J	B11			D40066J	A01			YD158-YR328
0267	24		PK		2-7	21-31-23	D41830J	B12			D40066J	A07			YD158-YR328
0268	22		CQ		2-5	34-24-15	D40328J	A03			TB4101X	A016	1A		YD158
0268	20		CQ		2-5	34-24-15	D40328J	A03			TB4101X	A016	1A		YL951-YR328
0271	24		B6		1-10	21-51-15	TB4101Y	A075	1A		D43018J	A10			YC051-YC055
0271	24		B6		1-11	21-51-15	TB4101Y	A075	1A		D43018J	A10			YC056-YR328
0272	24		B6		2-2	21-51-25	TB4101Y	A067	1A		D43044J	A09			YC051-YC055
0272	24		B6		2-3	21-51-25	TB4101Y	A067	1A		D43044J	A09			YC056-YR328
0273	24		B6		2-2	21-51-25	TB4101Y	A067	1A		D43044J	A10			YC051-YC055
0273	24		B6		2-3	21-51-25	TB4101Y	A067	1A		D43044J	A10			YC056-YR328
0274	24		B6		2-2	21-51-25	TB4101Y	A067	1A		D43044J	A04			YC051-YC055
0274	24		B6		2-3	21-51-25	TB4101Y	A067	1A		D43044J	A04			YC056-YR328
0280	24		PK		2-4	31-35-05	D40904J	A07			TB4101Y	B083	1A		YL963-YL999, YN236-YR328
0281	24		PK		2-4	31-35-05	D40904J	A08			TB4101Y	A083	1A		YL963-YL999, YN236-YR328
0284	24		PK		2-1	36-21-11	D43038J	B09			TB4101Y	B083	1A		YL963-YL999, YN236-YR328
0286	24		PK		2-1	36-21-11	D43038J	A10			TB4101Y	A083	1A		YL963-YL999, YN236-YR328
0291	20		PA		2-11	23-32-21	SP00291		W		D41830J	CAP	Y		YL968-YL999
0291	20		PA		3-5	23-32-21	SP00291		W		D40534J	CAP	Y		YN236-YN260
0301	24		B6		2-4	21-51-11	D40554J	A02			TB4101Z	B045	1A		YC051-YC055
0301	24		B6		2-5	21-51-11	D40554J	A02			TB4101Z	B045	1A		YC056-YL999, YR301-YR328
0302	24		B6		2-0	21-51-11	D40554J	A10			D00458A	18			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W0410

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0410	286A0410				E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)										
0302	24		B6		1-10	21-51-11	D40554J	A10			D00458A	18			YC056-YL999, YR301-YR328
0303	24		B6		2-0	21-51-11	D40554J	B10			D00458A	44			YC051-YC055
0303	24		B6		1-10	21-51-11	D40554J	B10			D00458A	44			YC056-YL999, YR301-YR328
0304	24		B6		2-4	21-51-11	D40554J	A13			TB4101Y	A049	1A		YC051-YC055
0304	24		B6		2-6	21-51-11	D40554J	A04			TB4101Y	A049	1A		YC056-YL999, YR301-YR328
0305	24		B6		2-6	21-51-11	TB4101Y	A073	1A		D00458A	43			YC051-YL999, YR301-YR328
0306	24		B6		2-6	21-51-11	D00458A	32			TB4101Y	B073	1A		YC051-YL999, YR301-YR328
0307	24		B6		2-11	21-51-11	D00458B	26			TB4101Y	A049	1A		YC051-YL999, YR301-YR328
0308	24		B6		2-11	21-51-11	D00458B	30			TB4101Y	B049	1A		YC051-YL999, YR301-YR328
0309	20		CQ		2-5	21-51-11	D00458B	4			GD04103	ST..	1A		YC051-YL999, YR301-YR328
0310	24		B6		2-11	21-51-11	D00458A	55			TB4101Z	B045	1A		YC051-YL999, YR301-YR328
0311	24		B6		2-11	21-51-11	D00458A	33			TB4101Z	A041	1A		YC051-YL999, YR301-YR328
0312	20		CQ		2-0	21-51-11	D00458A	45			GD04104	DC..	1A		YC051-YL999, YR301-YR328
0313	24		B6		2-7	21-51-11	D00458A	19			TB4101Y	B061	1A		YC051-YL999, YR301-YR328
0314	24		B6		2-10	21-51-11	D10002B	32			TB4101Z	A041	1A		YC051-YL999, YR301-YR328
0315	24		G6		2-2	21-51-12	D41828J	A01			D40244J	B07			YC051-YL999, YR301-YR328
0316	24		G6		1-11	21-51-12	D40534J	A16			D00458A	46			YC051-YL999, YR301-YR328
0317	24		G6		1-11	21-51-12	D40534J	A20			D00458A	58			YC051-YL999, YR301-YR328
0318	24		G6		3-5	21-51-12	D41804J	A01			D00458A	56			YC051-YC055
0318	24		G6		3-3	21-51-12	D41804J	A01			D00458A	56			YC056-YL999, YR301-YR328
0319	24		G6		3-5	21-51-12	D41804J	A02			D00458A	65			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W0410

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W0410	286A0410				E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)												
0319	24		G6		3-3	21-51-12	D41804J		A02			D00458A	65			YC056-YL999, YR301-YR328	
0320	24		G6		3-5	21-51-12	D41804J		A03			D00458A	66			YC051-YC055	
0320	24		G6		3-3	21-51-12	D41804J		A03			D00458A	66			YC056-YL999, YR301-YR328	
0321	24		G6		2-9	21-51-12	D00458A		50			D40244J	B08			YC051-YC055	
0321	24		G6		2-6	21-51-12	D00458A		50			D40244J	B08			YC056-YL999, YR301-YR328	
0322	24		G6		2-9	21-51-12	D00458A		64			D40244J	B09			YC051-YC055	
0322	24		G6		2-6	21-51-12	D00458A		64			D40244J	B09			YC056-YL999, YR301-YR328	
0323	24		G6		2-9	21-51-12	D00458A		63			D40244J	B10			YC051-YC055	
0323	24		G6		2-6	21-51-12	D00458A		63			D40244J	B10			YC056-YL999, YR301-YR328	
0324	24		G6		2-1	21-51-14	D40378J		B09			D00458A	59			YC051-YC055	
0324	24		G6		2-0	21-51-14	D40378J		B09			D00458A	59			YC056-YL999, YR301-YR328	
0325	24		G6		1-10	21-51-14	D40328J		A04			TB4101Y	B051	1A		YC051-YC055	
0325	24		G6		1-11	21-51-14	D40328J		A04			TB4101Y	B051	1A		YC056-YL999, YR301-YR323, YR325-YR328	
0326	24		G6		2-3	21-51-14	D41804J		A04			TB4101Y	B051	1A		YC051-YC055	
0326	24		G6		2-1	21-51-14	D41804J		A04			TB4101Y	B051	1A		YC056-YL999, YR301-YR323, YR325-YR328	
0327	24		G6		3-0	21-51-14	TB4101Y		B051	1A		D00458A	49			YC051-YL999, YR301-YR323, YR325-YR328	
0328	24		G6		3-5	21-51-14	D41804J		A05			D00458A	61			YC051-YC055	
0328	24		G6		3-3	21-51-14	D41804J		A05			D00458A	61			YC056-YL999, YR301-YR323, YR325-YR328	
0329	24		G6		3-5	21-51-14	D41804J		A06			D00458A	47			YC051-YC055	
0329	24		G6		3-3	21-51-14	D41804J		A06			D00458A	47			YC056-YL999, YR301-YR323, YR325-YR328	
0330	24		G6		3-5	21-51-14	D41804J		A07			D00458A	12			YC051-YC055	

WIRE LIST

D280A108

91-21-11

Section W0410

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0410	286A0410				E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)										
0330	24		G6		3-3	21-51-14	D41804J	A07			D00458A	12			YC056-YL999, YR301-YR323, YR325-YR328
0331	24		G6		3-5	21-51-14	D41804J	A08			D00458A	13			YC051-YC055
0331	24		G6		3-3	21-51-14	D41804J	A08			D00458A	13			YC056-YL999, YR301-YR323, YR325-YR328
0332	20		G5		2-5	21-51-14	D00458B	3			GD04103	DC..	1A		YC051-YL999, YR301-YR328
0333	24		G6		2-8	21-51-14	D00458B	33			D44161J	A07			YC051-YC055
0333	24		G6		2-9	21-51-14	D00458B	33			D44161J	A07			YC056-YL999, YR301-YR323, YR325-YR328
0334	24		G6		2-1	21-51-14	D00458A	35			D40378J	A11			YC051-YC055
0334	24		G6		2-0	21-51-14	D00458A	35			D40378J	A11			YC056-YL999, YR301-YR323, YR325-YR328
0335	24		G6		2-9	21-51-14	D00458A	23			D40244J	A01			YC051-YC055
0335	24		G6		2-6	21-51-14	D00458A	23			D40244J	A01			YC056-YL999, YR301-YR323, YR325-YR328
0336	24		G6		2-9	21-51-14	D00458A	24			D40244J	A02			YC051-YC055
0336	24		G6		2-6	21-51-14	D00458A	24			D40244J	A02			YC056-YL999, YR301-YR323, YR325-YR328
0337	24		G6		2-9	21-51-14	D00458A	36			D40244J	A03			YC051-YC055
0337	24		G6		2-6	21-51-14	D00458A	36			D40244J	A03			YC056-YL999, YR301-YR323, YR325-YR328
0338	24		B6		2-1	21-51-15	D40378J	A12			D00458A	30			YC051-YC055
0338	24		B6		2-0	21-51-15	D40378J	A12			D00458A	30			YC056-YL999, YR301-YR328
0339	24		B6		2-0	21-51-15	D40554J	B11			D00458B	36			YC051-YC055
0339	24		B6		1-10	21-51-15	D40554J	B07			D00458B	36			YC056-YL999, YR301-YR328
0340	24		PK		2-0	21-51-15	D40554J	A12			D00458B	23			YC051-YC055
0340	24		PK		1-10	21-51-15	D40554J	A07			D00458B	23			YC056-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11
Section W0410
Page 13
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W0410	286A0410				E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)												
0341	20		CQ		2-0	21-51-15		D00458B	60			GD04104	DC..	1A		YC051-YL999, YR301-YR328	
0342	24		B6		2-6	21-51-15		D00458B	35			TB4101Y	A075	1A		YC051-YL999, YR301-YR328	
0343	24		B6		2-10	21-51-21		D40562J	B06			TB4101Y	B049	1A		YC051-YL999, YR301-YR328	
0344	24		B6		2-10	21-51-21		D10002A	55			TB4101Y	B049	1A		YC051-YL999, YR301-YR328	
0345	24		B6		1-11	21-51-21		D40562J	B02			D10002A	18			YC051-YL999, YR301-YR328	
0346	24		B6		1-11	21-51-21		D40562J	A03			D10002A	44			YC051-YL999, YR301-YR328	
0347	24		B6		3-8	21-51-21		D10002A	32			TB4102Y	A019	1A		YC051-YC055	
0347	24		B6		3-10	21-51-21		D10002A	32			TB4102Y	A019	1A		YC056-YL999, YR301-YR328	
0348	24		B6		3-8	21-51-21		D10002A	43			TB4102Y	B019	1A		YC051-YC055	
0348	24		B6		3-10	21-51-21		D10002A	43			TB4102Y	B019	1A		YC056-YL999, YR301-YR328	
0349	24		B6		2-10	21-51-21		D10002B	26			TB4101Y	A049	1A		YC051-YL999, YR301-YR328	
0350	24		B6		2-10	21-51-21		D10002B	30			TB4101Z	B045	1A		YC051-YL999, YR301-YR328	
0351	20		CQ		2-4	21-51-21		D10002B	4			GD04103	ST..	1A		YC051-YL999, YR301-YR328	
0352	24		B6		2-10	21-51-21		D10002A	33			TB4101Z	A045	1A		YC051-YL999, YR301-YR328	
0353	24		B6		2-4	21-51-21		D10002A	19			TB4101Y	A069	1A		YC051-YL999, YR301-YR328	
0354	20		CQ		1-11	21-51-21		D10002A	45			GD04104	DC..	1A		YC051-YL999, YR301-YR328	
0355	24		B6		2-11	21-51-21		D00458B	32			TB4101Z	A045	1A		YC051-YL999, YR301-YR328	
0356	24		PK		3-2	21-51-22		D41830J	A01			D43038J	A12			YC051-YC055	
0356	24		PK		2-11	21-51-22		D41830J	A01			D43038J	A12			YC056-YL999, YR301-YR328	
0357	24		PK		1-10	21-51-22		D40542J	B09			D10002A	46			YC051-YC055	
0357	24		PK		1-8	21-51-22		D40542J	B09			D10002A	46			YC056-YL999, YR301-YR328	
0358	24		PK		1-10	21-51-22		D40542J	A09			D10002A	58			YC051-YC055	

WIRE LIST

D280A108

91-21-11

Section W0410

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W0410	286A0410				E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)											
0358	24		PK		1-8	21-51-22		D40542J	A09			D10002A	58			YC056-YL999, YR301-YR328
0359	24		PK		3-3	21-51-22		D41810J	A01			D10002A	56			YC051-YC055
0359	24		PK		3-1	21-51-22		D41810J	A01			D10002A	56			YC056-YL999, YR301-YR328
0360	24		PK		3-3	21-51-22		D41810J	A02			D10002A	65			YC051-YC055
0360	24		PK		3-1	21-51-22		D41810J	A02			D10002A	65			YC056-YL999, YR301-YR328
0361	24		PK		3-3	21-51-22		D41810J	A03			D10002A	66			YC051-YC055
0361	24		PK		3-1	21-51-22		D41810J	A03			D10002A	66			YC056-YL999, YR301-YR328
0362	24		PK		1-11	21-51-22		D10002A	50			D43038J	A13			YC051-YC055
0362	24		PK		1-10	21-51-22		D10002A	50			D43038J	A13			YC056-YL999, YR301-YR328
0363	24		PK		1-11	21-51-22		D10002A	64			D43038J	A14			YC051-YC055
0363	24		PK		1-10	21-51-22		D10002A	64			D43038J	A14			YC056-YL999, YR301-YR328
0364	24		PK		1-11	21-51-22		D10002A	63			D43038J	A15			YC051-YC055
0364	24		PK		1-10	21-51-22		D10002A	63			D43038J	A15			YC056-YL999, YR301-YR328
0365	24		PK		1-9	21-51-24		D40390J	B07			D10002A	59			YC051-YC055
0365	24		PK		1-8	21-51-24		D40390J	B07			D10002A	59			YC056-YL999, YR301-YR328
0366	24		PK		2-6	21-51-24		D40390J	B20			TB4101Y	B053	1A		YC051-YC055
0366	24		PK		2-5	21-51-24		D40390J	B20			TB4101Y	B053	1A		YC056-YL999, YR301-YR323, YR325-YR328
0367	24		PK		2-6	21-51-24		D41810J	A04			TB4101Y	B053	1A		YC051-YC055
0367	24		PK		2-4	21-51-24		D41810J	A04			TB4101Y	B053	1A		YC056-YL999, YR301-YR323, YR325-YR328
0368	24		PK		2-6	21-51-24		TB4101Y	B053	1A		D10002A	49			YC051-YL999, YR301-YR323, YR325-YR328
0369	24		PK		3-3	21-51-24		D41810J	A05			D10002A	61			YC051-YC055
0369	24		PK		3-1	21-51-24		D41810J	A05			D10002A	61			YC056-YL999, YR301-YR323, YR325-YR328
0370	24		PK		3-3	21-51-24		D41810J	A06			D10002A	47			YC051-YC055

WIRE LIST

D280A108

91-21-11
Section W0410
Page 15
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W0410	286A0410				E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)											
0370	24		PK		3-1	21-51-24		D41810J	A06			D10002A	47			YC056-YL999, YR301-YR323, YR325-YR328
0371	24		PK		3-3	21-51-24		D41810J	A07			D10002A	12			YC051-YC055
0371	24		PK		3-1	21-51-24		D41810J	A07			D10002A	12			YC056-YL999, YR301-YR323, YR325-YR328
0372	24		PK		3-3	21-51-24		D41810J	A08			D10002A	13			YC051-YC055
0372	24		PK		3-1	21-51-24		D41810J	A08			D10002A	13			YC056-YL999, YR301-YR323, YR325-YR328
0373	24		PK		1-9	21-51-24		D10002B	33			D40390J	B04			YC051-YC055
0373	24		PK		1-7	21-51-24		D10002B	33			D40390J	B04			YC056-YL999, YR301-YR323, YR325-YR328
0374	20		PA		1-11	21-51-24		D10002B	3			GD04104	DC..	1A		YC051-YL999, YR301-YR328
0375	24		PK		1-9	21-51-24		D10002A	35			D40390J	B05			YC051-YC055
0375	24		PK		1-8	21-51-24		D10002A	35			D40390J	B05			YC056-YL999, YR301-YR323, YR325-YR328
0376	24		PK		1-11	21-51-24		D10002A	23			D43038J	A02			YC051-YC055
0376	24		PK		1-10	21-51-24		D10002A	23			D43038J	A02			YC056-YL999, YR301-YR323, YR325-YR328
0377	24		PK		1-11	21-51-24		D10002A	24			D43038J	B02			YC051-YC055
0377	24		PK		1-10	21-51-24		D10002A	24			D43038J	B02			YC056-YL999, YR301-YR323, YR325-YR328
0378	24		PK		1-11	21-51-24		D10002A	36			D43038J	A03			YC051-YC055
0378	24		PK		1-10	21-51-24		D10002A	36			D43038J	A03			YC056-YL999, YR301-YR323, YR325-YR328
0379	24		B6		3-1	21-51-25		D41830J	A02			D10002A	30			YC051-YC055
0379	24		B6		2-10	21-51-25		D41830J	A02			D10002A	30			YC056-YL999, YR301-YR328
0380	24		B6		1-11	21-51-25		D40562J	B13			D10002B	23			YC051-YC055
0380	24		B6		1-10	21-51-25		D40562J	B13			D10002B	23			YC056-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W0410

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0410	286A0410				E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)										
0381	20		CQ		1-11	21-51-25	D10002B		60		GD04104	DC..	1A		YC051-YL999, YR301-YR328
0382	24		B6		1-11	21-51-25	D40562J		B04		D10002B		36		YC051-YC055
0382	24		B6		1-10	21-51-25	D40562J		B04		D10002B		36		YC056-YL999, YR301-YR328
0383	24		B6		2-4	21-51-25	D10002B		35		TB4101Y	A067	1A		YC051-YL999, YR301-YR328
0384	24		PK		3-2	21-61-11	D41828J		A02		D00458B		19		YC051-YC055
0384	24		PK		3-0	21-61-11	D41828J		A02		D00458B		19		YC056-YL999, YR301-YR328
0385	24		PK		1-3	21-61-11	D41804J		B01		TB4102Y	B003	1A		YC051-YC055
0385	24		PK		2-11	21-61-11	D41804J		B01		TB4102Y	B003	1A		YC056-YL999, YR301-YR328
0386	24		PK		3-3	21-61-11	D40534J		A15		TB4102Y	A001	1A		YC051-YC055
0386	24		PK		3-10	21-61-11	D40534J		A15		TB4102Y	A001	1A		YC056-YL999, YR301-YR328
0387	24		PK		1-3	21-61-11	D41804J		B02		TB4102Y	B001	1A		YC051-YC055
0387	24		PK		2-11	21-61-11	D41804J		B02		TB4102Y	B001	1A		YC056-YL999, YR301-YR328
0388	24		PK		3-5	21-61-11	D41804J		B03		D00458A		25		YC051-YC055
0388	24		PK		3-3	21-61-11	D41804J		B03		D00458A		25		YC056-YL999, YR301-YR328
0389	24		PK		3-5	21-61-11	D41804J		B04		D00458A		37		YC051-YC055
0389	24		PK		3-3	21-61-11	D41804J		B04		D00458A		37		YC056-YL999, YR301-YR328
0390	24		PK		3-5	21-61-11	D41804J		B05		D00458A		16		YC051-YC055
0390	24		PK		3-3	21-61-11	D41804J		B05		D00458A		16		YC056-YL999, YR301-YR328
0391	24		PK		3-6	21-61-11	D00458B		22		TB4102Y	A005	1A		YC051-YC055
0391	24		PK		3-11	21-61-11	D00458B		22		TB4102Y	A005	1A		YC056-YL999, YR301-YR328
0392	24		PK		0-11	21-61-11	TB4102Y		A003	1A	TB4102Y	A005	1A		YC051-YC055
0392	24		PK		1-3	21-61-11	TB4102Y		A003	1A	TB4102Y	A005	1A		YC056-YL999, YR301-YR328
0393	24		PK		3-5	21-61-11	D00458B		62		TB4102Y	B001	1A		YC051-YC055
0393	24		PK		4-0	21-61-11	D00458B		62		TB4102Y	B001	1A		YC056-YL999, YR301-YR328
0394	24		G6		4-0	21-51-12	D41828J		A03		D00458A		22		YC053-YC059

WIRE LIST

D280A108

91-21-11

Section W0410

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0410	286A0410				E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)										
0394	24		G6		3-1	21-51-12	D41828J	A03			D00458A	22			YC065-YL999, YR301-YR328
0395	24		PK		2-11	21-61-11	D00458A	57			TB4101Z	B045	1A		YC051-YL999, YR301-YR328
0396	24		PK		1-10	21-61-11	D00458B	41			D10002A	27			YC051-YL999, YR301-YR328
0397	24		PK		1-10	21-61-11	D00458B	42			D10002A	26			YC051-YL999, YR301-YR328
0398	24		PK		2-6	21-61-11	D10002B	41			TB4101Y	A055	1A		YC051-YL999, YR301-YR328
0399	24		PK		2-8	21-61-11	D00458B	61			D40328J	A02			YC051-YC055
0399	24		PK		2-5	21-61-11	D00458B	61			D40328J	A02			YC056-YL999, YR301-YR328
0400	24		PK		0-7	21-61-11	D00458B	43			D00458B	44			YC051-YL999, YR301-YR328
0401	24		PK		4-0	21-51-22	D41830J	B04			D10002A	22			YC053-YC059
0401	24		PK		2-10	21-51-22	D41830J	B04			D10002A	22			YC065-YL999, YR301-YR328
0402	24		PK		0-7	21-61-11	D00458A	27			D00458A	38			YC051-YL999, YR301-YR328
0403	24		PK		2-0	21-61-11	D00458A	41			D43018J	B06			YC051-YC055
0403	24		PK		1-9	21-61-11	D00458A	41			D43018J	B06			YC056-YL999, YR301-YR328
0404	24		PK		2-0	21-61-11	D00458A	42			D43018J	B07			YC051-YC055
0404	24		PK		1-9	21-61-11	D00458A	42			D43018J	B07			YC056-YL999, YR301-YR328
0405	24		PK		0-7	21-61-11	D00458A	26			D00458A	40			YC051-YL999, YR301-YR328
0406	24		PK		1-11	21-61-11	D43018J	B08			TB4101Y	A055	1A		YC051-YC055
0406	24		PK		2-1	21-61-11	D43018J	B08			TB4101Y	A055	1A		YC056-YL999, YR301-YR328
0407	24		PK		2-8	21-61-11	D00458A	28			TB4101Y	A055	1A		YC051-YL999, YR301-YR328
0408	24		PK		2-6	21-61-12	D40534J	A17			TB4101Y	B055	1A		YC051-YC055
0408	24		PK		2-5	21-61-12	D40534J	A17			TB4101Y	B055	1A		YC056-YL999, YR301-YR328
0409	24		PK		2-7	21-61-12	D41804J	B08			TB4101Y	B055	1A		YC051-YC055
0409	24		PK		2-5	21-61-12	D41804J	B08			TB4101Y	B055	1A		YC056-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W0410

Page 18

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number		Fam	Description		From			To			Effectivity		
Wire No.		GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W0410		286A0410			E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)										
0410		24	PK		3-4	21-61-12	D41804J	B07			D10002A	25			YC051-YC055
0410		24	PK		3-2	21-61-12	D41804J	B07			D10002A	25			YC056-YL999, YR301-YR328
0411		24	PK		3-4	21-61-12	D41804J	B06			D10002A	37			YC051-YC055
0411		24	PK		3-2	21-61-12	D41804J	B06			D10002A	37			YC056-YL999, YR301-YR328
0412		24	PK		2-6	21-61-12	D10002A	16			TB4101Y	B055	1A		YC051-YL999, YR301-YR328
0413		24	PK		2-3	21-61-13	D41810J	B01			TB4102Y	B009	1A		YC051-YC055
0413		24	PK		2-9	21-61-13	D41810J	B01			TB4102Y	B009	1A		YC056-YL999, YR301-YR328
0414		24	PK		3-6	21-61-13	D40542J	A10			TB4102Y	A007	1A		YC051-YC055
0414		24	PK		3-9	21-61-13	D40542J	A10			TB4102Y	A007	1A		YC056-YL999, YR301-YR328
0415		24	PK		2-5	21-61-13	D40542J	A11			TB4101Y	B067	1A		YC051-YC055
0415		24	PK		2-4	21-61-13	D40542J	A11			TB4101Y	B067	1A		YC056-YL999, YR301-YR328
0416		24	PK		2-2	21-61-13	D41810J	B02			TB4102Y	B007	1A		YC051-YC055
0416		24	PK		2-9	21-61-13	D41810J	B02			TB4102Y	B007	1A		YC056-YL999, YR301-YR328
0417		24	PK		2-8	21-61-13	D41810J	B03			TB4101Y	B067	1A		YC051-YC055
0417		24	PK		2-6	21-61-13	D41810J	B03			TB4101Y	B067	1A		YC056-YL999, YR301-YR328
0418		24	PK		3-3	21-61-13	D41810J	B04			D10002A	54			YC051-YC055
0418		24	PK		3-1	21-61-13	D41810J	B04			D10002A	54			YC056-YL999, YR301-YR328
0419		24	PK		3-3	21-61-13	D41810J	B05			D10002A	53			YC051-YC055
0419		24	PK		3-1	21-61-13	D41810J	B05			D10002A	53			YC056-YL999, YR301-YR328
0420		24	PK		3-6	21-61-13	D10002B	34			TB4102Y	A011	1A		YC051-YC055
0420		24	PK		3-9	21-61-13	D10002B	34			TB4102Y	A011	1A		YC056-YL999, YR301-YR328
0421		24	PK		0-7	21-61-13	TB4102Y	A011	1A		TB4102Y	A009	1A		YC051-YL999, YR301-YR328
0422		24	PK		3-5	21-61-13	D10002B	49			TB4102Y	B007	1A		YC051-YC055
0422		24	PK		3-10	21-61-13	D10002B	49			TB4102Y	B007	1A		YC056-YL999, YR301-YR328
0423		24	PK		2-5	21-61-13	D10002A	11			TB4101Y	B067	1A		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W0410

Page 19

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0410	286A0410			E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)											
0424	24		PK		3-2	21-61-13	D10002B	48			D41816J	A01			YC051-YC055
0424	24		PK		3-0	21-61-13	D10002B	48			D41816J	A01			YC056-YL999, YR301-YR328
0426	24		PK		2-4	21-61-13	D10002A	52			D43044J	B08			YC051-YC055
0426	24		PK		2-3	21-61-13	D10002A	52			D43044J	B08			YC056-YL999, YR301-YR328
0427	24		PK		2-4	21-61-13	D10002A	51			D43044J	B09			YC051-YC055
0427	24		PK		2-3	21-61-13	D10002A	51			D43044J	B09			YC056-YL999, YR301-YR328
0428	24		PK		2-4	21-61-13	D10002A	67			D43044J	B10			YC051-YC055
0428	24		PK		2-3	21-61-13	D10002A	67			D43044J	B10			YC056-YL999, YR301-YR328
0429	24		B6		3-2	21-61-14	D41830J	B02			D00458B	20			YC051-YC055
0429	24		B6		2-11	21-61-14	D41830J	B02			D00458B	20			YC056-YL999, YR301-YR328
0430	24		PK		2-4	21-61-14	D41810J	B06			TB4102Y	B015	1A		YC051-YC055
0430	24		PK		2-9	21-61-14	D41810J	B06			TB4102Y	B015	1A		YC056-YL999, YR301-YR328
0431	24		PK		3-6	21-61-14	D40534J	A19			TB4102Y	A013	1A		YC051-YC055
0431	24		PK		3-8	21-61-14	D40534J	A19			TB4102Y	A013	1A		YC056-YL999, YR301-YR328
0432	24		PK		2-5	21-61-14	D40534J	A18			TB4101Y	A059	1A		YC051-YL999, YR301-YR328
0433	24		PK		2-4	21-61-14	D41810J	B07			TB4102Y	B013	1A		YC051-YC055
0433	24		PK		2-9	21-61-14	D41810J	B07			TB4102Y	B013	1A		YC056-YL999, YR301-YR328
0434	24		PK		2-6	21-61-14	D41810J	B08			TB4101Y	A059	1A		YC051-YC055
0434	24		PK		2-4	21-61-14	D41810J	B08			TB4101Y	A059	1A		YC056-YL999, YR301-YR328
0435	24		PK		3-4	21-61-14	D41810J	B09			D00458A	54			YC051-YC055
0435	24		PK		3-2	21-61-14	D41810J	B09			D00458A	54			YC056-YL999, YR301-YR328
0436	24		PK		3-4	21-61-14	D41810J	B10			D00458A	53			YC051-YC055
0436	24		PK		3-2	21-61-14	D41810J	B10			D00458A	53			YC056-YL999, YR301-YR328
0437	24		PK		3-9	21-61-14	D00458B	34			TB4102Y	A017	1A		YC051-YC055
0437	24		PK		3-11	21-61-14	D00458B	34			TB4102Y	A017	1A		YC056-YL999, YR301-YR328
0438	24		PK		0-11	21-61-14	TB4102Y	A017	1A		TB4102Y	A015	1A		YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W0410

Page 20

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W0410	286A0410				E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)										
0438	24		PK		1-1	21-61-14	TB4102Y	A017	1A		TB4102Y	A015	1A		YC056-YL999, YR301-YR328
0439	24		PK		3-8	21-61-14	D00458B	49			TB4102Y	B013	1A		YC051-YC055
0439	24		PK		3-10	21-61-14	D00458B	49			TB4102Y	B013	1A		YC056-YL999, YR301-YR328
0440	24		PK		2-7	21-61-14	D00458A	11			TB4101Y	A059	1A		YC051-YL999, YR301-YR328
0441	24		PK		3-3	21-61-14	D00458B	48			D41816J	A02			YC051-YC055
0441	24		PK		3-1	21-61-14	D00458B	48			D41816J	A02			YC056-YL999, YR301-YR328
0443	24		PK		2-5	21-61-14	D00458A	52			D43044J	A05			YC051-YC055
0443	24		PK		2-4	21-61-14	D00458A	52			D43044J	A05			YC056-YL999, YR301-YR328
0444	24		PK		2-5	21-61-14	D00458A	51			D43044J	A06			YC051-YC055
0444	24		PK		2-4	21-61-14	D00458A	51			D43044J	A06			YC056-YL999, YR301-YR328
0445	24		PK		2-5	21-61-14	D00458A	67			D43044J	B06			YC051-YC055
0445	24		PK		2-4	21-61-14	D00458A	67			D43044J	B06			YC056-YL999, YR301-YR328
0446	24		PK		0-11	21-61-15	TB4102Y	B005	1A		TB4102Y	B011	1A		YC051-YC055
0446	24		PK		1-1	21-61-15	TB4102Y	B005	1A		TB4102Y	B011	1A		YC056-YL999, YR301-YR328
0447	24		PK		1-0	21-61-15	TB4102Y	B011	1A		TB4102Y	B017	1A		YC051-YC055
0447	24		PK		1-3	21-61-15	TB4102Y	B011	1A		TB4102Y	B017	1A		YC056-YL999, YR301-YR328
0448	24		PK		2-2	21-61-15	D41810J	A09			TB4102Y	B005	1A		YC051-YC055
0448	24		PK		2-9	21-61-15	D41810J	A09			TB4102Y	B005	1A		YC056-YL999, YR301-YR328
0449	24		PK		2-7	21-61-51	D40534J	B18			D40244J	A08			YC051-YC055
0449	24		PK		2-4	21-61-51	D40534J	B18			D40244J	A08			YC056-YL999, YR301-YR328
0450	24		PK		2-6	21-61-51	D40534J	B15			D40328J	A09			YC051-YC055
0450	24		PK		2-3	21-61-51	D40534J	B15			D40328J	A09			YC056-YL999, YR301-YR328
0451	24		PK		1-11	21-61-51	D40534J	B16			D43038J	B10			YC051-YC055
0451	24		PK		1-10	21-61-51	D40534J	B16			D43038J	B10			YC056-YL999, YR301-YR328
0452	24		PK		1-10	36-11-11	D40542J	B13			D10002A	8			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W0410

Page 21

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type		Splice
W0410	286A0410				E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)											
0452	24		PK		1-8	36-11-11	D40542J		B13			D10002A	8			YC056-YL999, YR301-YR328
0453	24		PK		1-10	36-11-11	D40542J		A14			D10002B	45			YC051-YC055
0453	24		PK		1-8	36-11-11	D40542J		A14			D10002B	45			YC056-YL999, YR301-YR328
0454	24		G6		1-11	36-11-11	D40534J		B04			D00458B	45			YC051-YL999, YR301-YR328
0455	24		G6		1-11	36-11-11	D40534J		A05			D00458A	8			YC051-YL999, YR301-YR328
0456	24		PK		3-9	36-11-11	D10002A		1			TB4102Y	A021	1A		YC051-YC055
0456	24		PK		3-11	36-11-11	D10002A		1			TB4102Y	A021	1A		YC056-YL999, YR301-YR328
0457	24		PK		1-10	36-11-11	D10002A		2			D40156J	A02			YC051-YC055
0457	24		PK		1-9	36-11-11	D10002A		2			D40156J	A02			YC056-YL999, YR301-YR328
0458	24		PK		2-4	36-11-11	D10002A		5			TB4101Y	B069	1A		YC051-YL999, YR301-YR328
0459	24		PK		1-10	36-11-11	D10002B		24			D40156J	B02			YC051-YC055
0459	24		PK		1-9	36-11-11	D10002B		24			D40156J	B02			YC056-YL999, YR301-YR328
0460	24		G6		2-0	36-11-11	D00458B		24			D40378J	A16			YC051-YL999, YR301-YR328
0461	24		G6		2-1	36-11-11	D00458A		5			D40378J	A13			YC051-YC055
0461	24		G6		2-0	36-11-11	D00458A		5			D40378J	A13			YC056-YL999, YR301-YR328
0462	24		G6		2-1	36-11-11	D00458A		2			D40378J	A15			YC051-YC055
0462	24		G6		2-0	36-11-11	D00458A		2			D40378J	A15			YC056-YL999, YR301-YR328
0463	24		G6		0-7	36-11-11	D00458A		1			SM00001		W		YC051-YL999, YR301-YR328
0464	24		PK		2-2	21-25-11	TB4101Z		B041	1A		D40330J	3			YC051-YC055
0464	24		PK		2-4	21-25-11	TB4101Z		B041	1A		D40330J	3			YC056-YL999, YR301-YR328
0465	24		PK		2-6	21-25-11	D00458B		14			TB4101Y	B075	1A		YC051-YL999, YR301-YR328
0466	24		PK		3-10	21-25-11	D00458B		15			TB4102Y	B021	1A		YC051-YC055
0466	24		PK		4-0	21-25-11	D00458B		15			TB4102Y	B021	1A		YC056-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W0410

Page 22

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W0410	286A0410				E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)											
0467	24		PK		1-10	21-25-11		D00458B				D10002A	29			YC051-YL999, YR301-YR328
0468	24		PK		1-10	21-25-11		D00458B				D10002A	17			YC051-YL999, YR301-YR328
0469	24		PK		1-10	21-25-11		D00458B				D10002A	15			YC051-YL999, YR301-YR328
0470	24		PK		2-5	21-25-11		TB4101Y	B075	1A		D10002A	14			YC051-YL999, YR301-YR328
0471	24		PK		3-9	21-25-11		D10002A		6		TB4102Y	B021	1A		YC051-YC055
0471	24		PK		3-11	21-25-11		D10002A		6		TB4102Y	B021	1A		YC056-YL999, YR301-YR328
0472	24		PK		2-5	21-25-11		TB4101Y	B075	1A		D10002A	9			YC051-YL999, YR301-YR328
0473	24		B6		3-1	21-61-13		D41830J	B01			D10002B	20			YC051-YC055
0473	24		B6		2-10	21-61-13		D41830J	B01			D10002B	20			YC056-YL999, YR301-YR328
0474	24		PK		3-2	21-25-11		D40554J	B12			TB4102Y	B021	1A		YC051-YC055
0474	24		PK		3-6	21-25-11		D40554J	B06			TB4102Y	B021	1A		YC056-YL999, YR301-YR328
0475	24		PK		2-1	21-25-11		D40244J	B04			TB4101Y	B075	1A		YC051-YC055
0475	24		PK		1-10	21-25-11		D40244J	B04			TB4101Y	B075	1A		YC056-YL999, YR301-YR328
0476	24		PK		2-4	21-25-11		D10002B	16			TB4101Y	B071	1A		YC051-YL999, YR301-YR328
0477	24		PK		2-4	21-25-11		D10002B	15			TB4101Y	B071	1A		YC051-YL999, YR301-YR328
0478	24		PK		2-10	21-25-11		D10002B	28			TB4101Z	B041	1A		YC051-YL999, YR301-YR328
0479	24		PK		2-10	21-25-11		D10002B	14			TB4101Z	B041	1A		YC051-YL999, YR301-YR328
0480	24		PK		1-10	21-25-11		D10002B	29			D00458A	29			YC051-YL999, YR301-YR328
0481	24		PK		2-6	21-25-11		D00458A	6			TB4101Y	B071	1A		YC051-YL999, YR301-YR328
0482	24		PK		2-11	21-25-11		D00458A	15			TB4101Z	B041	1A		YC051-YL999, YR301-YR328
0483	24		PK		2-11	21-25-11		D00458A	14			TB4101Z	B041	1A		YC051-YL999, YR301-YR328
0484	24		PK		2-3	21-25-11		D41010J	13			TB4101Z	B041	1A		YC051-YC055

WIRE LIST

D280A108

91-21-11
Section W0410
Page 23
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0410	286A0410			E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)											
0484	24		PK		2-7	21-25-11	D41010J		13		TB4101Z	B041	1A		YC056-YL999, YR301-YR328
0485	20		PA		2-1	30-71-11	D40378J		B19		D43038J	A16			YC051-YC055
0485	20		PA		2-0	30-71-11	D40378J		B19		D43038J	A16			YC056-YR328
0487	24		G6		2-9	34-61-17	D00458A		3		D44161J	A17			YC051-YL999, YR301-YR328
0488	20		G5		2-0	34-61-17	D00458A		4		GD04104	DC..	1A		YC051-YL999, YR301-YR328
0489	24		G6		2-8	34-61-17	D10002A		3		D44161J	A18			YC051-YL999, YR301-YR328
0490	20		G5		1-11	34-61-17	D10002A		4		GD04104	DC..	1A		YC051-YL999, YR301-YR328
0491	24		PK		3-6	31-31-17	D40390J		B10		TB4101X	B012	1A		YD158-YR328
0493	22		GA		1-7	21-31-23	D10740B		D07		GD04104	DC..	1A		YC051-YC052, YC054, YC056-YC059, YC065
0494	22		PA		1-7	21-31-23	D10740B		D08		GD04104	DC..	1A		YC051-YD157
0495	24		PK		2-8	31-31-17	D44161J		B15		TB4101X	A011	1A		YC051-YC055
0495	24		PK		2-7	31-31-17	D44161J		B15		TB4101X	A011	1A		YC056-YC065
0495	24		G6		2-7	31-31-17	D44161J		B15		TB4101X	A011	1A		YC067-YR328
0496	22		G5		2-8	23-51-51	TB4101X		A009	1A	D44161J	A08			YC051-YC055
0496	22		G5		2-7	23-51-51	TB4101X		A009	1A	D44161J	A08			YC056-YR328
0497	22		PA		2-8	23-51-51	TB4101X		B009	1A	D44161J	A20			YC051-YC055
0497	22		PA		2-7	23-51-51	TB4101X		B009	1A	D44161J	A20			YC056-YR328
1001	20		X1	AA	2-3	73-22-11	D40390J		A04		D40144J	A06			YC051-YC055
1001	20		X1	AA	2-0	73-22-11	D40390J		A04		D40144J	A06			YC056-YR328
1001Z				AA	0-0	73-22-11	D40390J	PERG	1F		D40144J	PERG	1F		ALL
1002	20		X1	AB	2-1	74-11-11	D43044J		A08		D40144J	A04			YC051-YC055
1002	20		X1	AB	2-0	74-11-11	D43044J		A08		D40144J	A04			YC056-YR328
1002Z				AB	0-0	74-11-11	D43044J	PERG	1F		D40144J	PERG	1F		ALL
1003	20		X1	AC	2-3	21-31-23	D40542J		A04		D40066J	A02			YC051-YC055
1003	20		X1	AC	2-0	21-31-23	D40542J		A04		D40066J	A02			YC056-YR328
1003Z				AC	0-0	21-31-23	D40542J	PERG	1F		D40066J	PERG	1F		ALL
1004	22		X1	AD	2-6	21-31-23	D40542J		B04		D10740A	D15			YC051-YC055
1004	22		X1	AD	2-5	21-31-23	D40542J		B04		D10740A	D15			YC056-YD157
1004Z				AD	0-0	21-31-23	D40542J	PERG	1F		D10740A	PERG	1A		YC051-YD157
1301R	20		X5	EN	2-0	26-11-21	D40328J		A10		D41010J	16			YC051-YC055
1301R	20		X5	EN	2-1	26-11-21	D40328J		A10		D41010J	16			YC056-YR328
1301Z				EN	0-0	26-11-21	D40328J		DED		D41010J	DED			ALL

WIRE LIST

D280A108

91-21-11

Section W0410

Page 24

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0410	286A0410				E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)										
1302R	20	X5	EP		2-0	26-11-21	D40328J	B10			D41010J	17			YC051-YC055
1302R	20	X5	EP		2-1	26-11-21	D40328J	B10			D41010J	17			YC056-YR328
1302Z			EP		0-0	26-11-21	D40328J	DED			D41010J	DED			ALL
1303R	20	X5	EQ		2-3	26-11-21	D40378J	B12			D40144J	B03			YC051-YC055
1303R	20	X5	EQ		2-2	26-11-21	D40378J	B12			D40144J	B03			YC056-YR328
1303Z			EQ		0-0	26-11-21	D40378J	DED			D40144J	DED			ALL
1304R	20	X5	ER		2-3	26-11-21	D40378J	B13			D40144J	A03			YC051-YC055
1304R	20	X5	ER		2-2	26-11-21	D40378J	B13			D40144J	A03			YC056-YR328
1304Z			ER		0-0	26-11-21	D40378J	DED			D40144J	DED			ALL
2001B	24	Y2	GA		2-4	34-21-14	D44161J	B11			TB4101Y	A023	1A		YC051-YC055
2001B	24	Y2	GA		2-3	34-21-14	D44161J	B11			TB4101Y	A023	1A		YC056-YD157
2001R	24	Y2	GA		0-0	34-21-14	D44161J	A11			TB4101Y	B021	1A		YC051-YD157
2001Z			GA		0-0	34-21-14	D44161J	PERG	1F		GB04101	ST..	1A		YC051-YD157
2002B	24	Y2	GB		3-1	34-21-24	D40390J	B02			TB4101Y	A037	1A		YC051-YC055
2002B	24	Y2	GB		2-11	34-21-24	D40390J	B02			TB4101Y	A037	1A		YC056-YD157
2002R	24	Y2	GB		0-0	34-21-24	D40390J	B01			TB4101Y	B033	1A		YC051-YD157
2002Z			GB		0-0	34-21-24	D40390J	PERG	1F		GB04101	ST..	1A		YC051-YD157
2003B	24	Y2	GC		1-11	27-32-12	D44161J	B02			TB4101Y	B057	1A		YC051-YD157
2003R	24	Y2	GC		0-0	27-32-12	D44161J	A02			TB4101Y	A057	1A		YC051-YD157
2003Z			GC		0-0	27-32-12	D44161J	PERG	1F		GB04101	ST..	1A		YC051-YD157
2004B	24	Y2	GD		2-5	27-32-22	D40390J	A06			TB4101Y	B065	1A		YC051-YC055
2004B	24	Y2	GD		2-3	27-32-22	D40390J	A06			TB4101Y	B065	1A		YC056-YD157
2004R	24	Y2	GD		0-0	27-32-22	D40390J	A05			TB4101Y	A065	1A		YC051-YD157
2004Z			GD		0-0	27-32-22	D40390J	PERG	1F		GB04101	ST..	1A		YC051-YD157
2005B	24	Y2	GE		1-8	73-24-12	D40390J	B16			D40156J	A07			YC051-YC055
2005B	24	Y2	GE		1-5	73-24-12	D40390J	B16			D40156J	A07			YC056-YR328
2005R	24	Y2	GE		0-0	73-24-12	D40390J	B15			D40156J	B07			ALL
2005Z			GE		0-0	73-24-12	D40390J	PERG	1F		D40156J	PERG	1F		ALL
2006B	20	X2	GF		1-8	73-24-21	D40390J	A08			D40156J	A06			YC051-YC055
2006B	20	X2	GF		1-5	73-24-21	D40390J	A08			D40156J	A06			YC056-YR328
2006R	20	X2	GF		0-0	73-24-21	D40390J	A09			D40156J	B06			ALL
2006Z			GF		0-0	73-24-21	D40390J	PERG	1F		D40156J	PERG	1F		ALL
2007B	24	Y2	GG		2-0	76-21-21	D40562J	B05			D40158J	A03			YC051-YC055
2007B	24	Y2	GG		1-9	76-21-21	D40562J	B05			D40158J	A03			YC056-YR328
2007R	24	Y2	GG		0-0	76-21-21	D40562J	A05			D40158J	B03			ALL
2007Z			GG		0-0	76-21-21	D40562J	DED			D40158J	DED			ALL
2008B	24	Y2	GH		2-0	77-12-21	D40390J	A12			D40158J	A08			YC051-YC055
2008B	24	Y2	GH		1-8	77-12-21	D40390J	A12			D40158J	A08			YC056-YR328
2008R	24	Y2	GH		0-0	77-12-21	D40390J	A11			D40158J	B08			ALL

WIRE LIST

D280A108

91-21-11

Section W0410

Page 25

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W0410	286A0410	E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)													
2008Z															
2009B	22	VX	GI	0-0	77-12-21	D40390J	PERG	1F	D40158J	PERG	1F		ALL		
2009B	22	VX	GI	1-8	77-31-21	D40390J	B11		D40156J	A04			YC051-YC055		
2009W	22	VX	GI	1-5	77-31-21	D40390J	B11		D40156J	A04			YC056-YR328		
2009Z	22		GI	0-0	77-31-21	D40390J	B12		D40156J	B04			ALL		
2010B	22	PB	GJ	0-0	77-31-21	D40390J	B13		D40156J	A05			ALL		
2010B	22	PB	GJ	1-8	78-36-21	D40390J	A14		D40156J	A08			YC051-YC055		
2010R	22	PB	GJ	1-5	78-36-21	D40390J	A14		D40156J	A08			YC056-YR328		
2011B	22	PB	GK	0-0	78-36-21	D40390J	A13		D40156J	B08			ALL		
2011B	22	PB	GK	1-8	78-36-21	D40390J	A16		D40156J	A13			YC051-YC055		
2011R	22	PB	GK	1-5	78-36-21	D40390J	A16		D40156J	A13			YC056-YR328		
2012B	24	Y2	GL	0-0	78-36-21	D40390J	A15		D40156J	B13			ALL		
2012B	24	Y2	GL	1-8	73-21-11	D40390J	B19		D40156J	A09			YC051-YC055		
2012R	24	Y2	GL	1-5	73-21-11	D40390J	B19		D40156J	A09			YC056-YR328		
2012Z	24		GL	0-0	73-21-11	D40390J	B18		D40156J	B09			ALL		
2013B	22	X2	GM	0-0	73-21-11	D40390J	PERG	1F	D40156J	PERG	1F		ALL		
2013B	22	X2	GM	2-1	21-31-11	D40554J	B08		D40242J	A02			YC051-YC055		
2013R	22	X2	GM	2-0	21-31-11	D40554J	B08		D40242J	A02			YC056-YR328		
2013Z	22		GM	0-0	21-31-11	D40554J	A08		D40242J	A01			ALL		
2014B	24	Y2	GN	0-0	21-31-11	D40554J	PERG	1F	D40242J	PERG	1F		ALL		
2014B	24	Y2	GN	2-5	21-31-23	D40542J	B05		D10740B	A08			YC051-YC055		
2014R	24	Y2	GN	2-4	21-31-23	D40542J	B05		D10740B	A08			YC056-YD157		
2014Z	24		GN	0-0	21-31-23	D40542J	A05		D10740B	A07			YC051-YD157		
2015B	24	Y2	GP	0-0	21-31-23	D40542J	PERG	1F	D10740B	PERG	1A		YC051-YD157		
2015B	24	Y2	GP	2-6	21-31-23	D40542J	B06		D10740A	A02			YC051-YC055		
2015R	24	Y2	GP	2-5	21-31-23	D40542J	B06		D10740A	A02			YC056-YD157		
2015Z	24		GP	0-0	21-31-23	D40542J	A06		D10740A	A01			YC051-YD157		
2016B	24	Y2	GQ	0-0	21-31-23	D40542J	PERG	1F	D10740A	PERG	1A		YC051-YD157		
2016B	24	Y2	GQ	2-2	21-31-23	D40066J	A04		D10740A	A08			YC051-YC055		
2016R	24	Y2	GQ	2-3	21-31-23	D40066J	A04		D10740A	A08			YC056-YD157		
2016Z	24		GQ	0-0	21-31-23	D40066J	A03		D10740A	A07			YC051-YD157		
2017B	24	Y2	GR	0-0	21-31-23	D40066J	PERG	1F	D10740A	PERG	1A		YC051-YD157		
2017B	24	Y2	GR	2-2	21-31-23	D40066J	A06		D10740A	A10			YC051-YC055		
2017R	24	Y2	GR	2-3	21-31-23	D40066J	A06		D10740A	A10			YC056-YD157		
2017Z	24		GR	0-0	21-31-23	D40066J	A05		D10740A	A09			YC051-YD157		
2018B	24	Y2	GS	0-0	21-31-23	D40066J	PERG	1F	D10740A	PERG	1A		YC051-YD157		
2018R	24	Y2	GS	2-11	21-31-24	D10740B	A04		TB4101Y	A023	1A		YC051-YD157		
2018Z	24		GS	0-0	21-31-24	D10740B	A03		TB4101Y	B021	1A		YC051-YD157		
2019B	24	Y2	GT	0-0	21-31-24	D10740B	PERG	1A	GB04101	ST..	1A		YC051-YD157		
				3-4	21-31-24	D40378J	A02		TB4101Y	A023	1A		YC051-YD157		

WIRE LIST

D280A108

91-21-11

Section W0410

Page 26

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W0410	286A0410	E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)													
2019R	24	Y2	GT	0-0	21-31-24	D40378J	A03		TB4101Y	B021	1A		YC051-YD157		
2019Z			GT	0-0	21-31-24	D40378J	PERG	1F	GB04101	ST..	1A		YC051-YD157		
2020B	24	Y2	GU	2-1	21-31-24	D10740B	A06		TB4101Y	B057	1A		YC051-YD157		
2020R	24	Y2	GU	0-0	21-31-24	D10740B	A05		TB4101Y	A057	1A		YC051-YD157		
2020Z			GU	0-0	21-31-24	D10740B	PERG	1A	GB04101	ST..	1A		YC051-YD157		
2021B	24	Y2	GV	2-7	21-31-24	D40378J	A04		TB4101Y	B057	1A		YC051-YC055		
2021B	24	Y2	GV	2-6	21-31-24	D40378J	A04		TB4101Y	B057	1A		YC056-YD157		
2021R	24	Y2	GV	0-0	21-31-24	D40378J	A05		TB4101Y	A057	1A		YC051-YD157		
2021Z			GV	0-0	21-31-24	D40378J	PERG	1F	GB04101	ST..	1A		YC051-YD157		
2022B	24	Y2	GW	2-8	21-31-24	D10740B	A10		TB4101Y	A037	1A		YC051-YD157		
2022R	24	Y2	GW	0-0	21-31-24	D10740B	A09		TB4101Y	B033	1A		YC051-YD157		
2022Z			GW	0-0	21-31-24	D10740B	PERG	1A	GB04101	ST..	1A		YC051-YD157		
2023B	24	Y2	GX	3-1	21-31-24	D40378J	A06		TB4101Y	A037	1A		YC051-YD157		
2023R	24	Y2	GX	0-0	21-31-24	D40378J	A07		TB4101Y	B033	1A		YC051-YD157		
2023Z			GX	0-0	21-31-24	D40378J	PERG	1F	GB04101	ST..	1A		YC051-YD157		
2024B	24	Y2	GY	2-0	21-31-24	D10740B	A14		TB4101Y	B065	1A		YC051-YD157		
2024R	24	Y2	GY	0-0	21-31-24	D10740B	A13		TB4101Y	A065	1A		YC051-YD157		
2024Z			GY	0-0	21-31-24	D10740B	PERG	1A	GB04101	ST..	1A		YC051-YD157		
2025B	24	Y2	GZ	2-5	21-31-24	D40378J	A08		TB4101Y	B065	1A		YC051-YD157		
2025R	24	Y2	GZ	0-0	21-31-24	D40378J	A09		TB4101Y	A065	1A		YC051-YD157		
2025Z			GZ	0-0	21-31-24	D40378J	PERG	1F	GB04101	ST..	1A		YC051-YD157		
2026B	24	Y2	HA	2-4	31-22-11	D44161J	B01		TB4101Y	A017	1A		YC051-YC055		
2026B	24	Y2	HA	2-3	31-22-11	D44161J	B01		TB4101Y	A017	1A		YC056-YR328		
2026R	24	Y2	HA	0-0	31-22-11	D44161J	A01		TB4101Y	B017	1A		ALL		
2026Z			HA	0-0	31-22-11	D44161J	PERG	1F	GB04101	ST..	1A		ALL		
2027B	24	Y2	HB	2-4	31-22-11	D44161J	B03		TB4101Y	A017	1A		YC051-YC055		
2027B	24	Y2	HB	2-3	31-22-11	D44161J	B03		TB4101Y	A017	1A		YC056-YR328		
2027R	24	Y2	HB	0-0	31-22-11	D44161J	A03		TB4101Y	B017	1A		ALL		
2027Z			HB	0-0	31-22-11	D44161J	PERG	1F	GB04101	ST..	1A		ALL		
2028B	22	M2	HC	2-4	34-45-21	D44161J	A13		TB4101Y	A019	1A		YC051-YC055		
2028B	22	M2	HC	2-3	34-45-21	D44161J	A13		TB4101Y	A019	1A		YC056-YR328		
2028R	22	M2	HC	0-0	34-45-21	D44161J	A12		TB4101Y	B019	1A		ALL		
2028ZI			HC	0-0	34-45-21	D44161J	A14		TB4101Y	A021	1A		ALL		
2028ZO			HC	0-0	34-45-21	D44161J	PERG	1F	GB04101	ST..	1A		ALL		
2035B	24	Y2	HJ	2-5	21-31-23	D44161J	B05		D40066J	A04			YD158-YR328		
2035R	24	Y2	HJ	0-0	21-31-23	D44161J	A05		D40066J	A03			YD158-YR328		
2035Z			HJ	0-0	21-31-23	D44161J	PERG	1F	D40066J	PERG	1F		YD158-YR328		
2036B	24	Y2	HK	2-5	21-31-23	D44161J	B18		D40066J	A06			YD158-YR328		
2036R	24	Y2	HK	0-0	21-31-23	D44161J	B14		D40066J	A05			YD158-YR328		

WIRE LIST

D280A108

91-21-11

Section W0410

Page 27

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice
W0410	286A0410				E4-1 SHELF (ELECTRICAL EQUIPMENT) RB2 (continued)										
2036Z				HK	0-0	21-31-23	D44161J	PERG	1F		D40066J	PERG	1F	YD158-YR328	
2041B	20	X2		AJ	2-7	31-35-05	D44161J		B07		D40156J		B16	YL963-YL999, YN236-YR328	
2041R	20	X2		AJ	0-0	31-35-05	D44161J		B06		D40156J		A16	YL963-YL999, YN236-YR328	
2041Z				AJ	0-0	31-35-05	D44161J	PERG	1F		D40156J	PERG	1F	YL963-YL999, YN236-YR328	
2201B	22	PB		KA	2-9	24-41-11	D41010J		9		TB4101X	A014	1A	YC051-YC055	
2201B	22	PB		KA	3-1	24-41-11	D41010J		9		TB4101X	A014	1A	YC056-YR328	
2201R	22	PB		KA	0-0	24-41-11	D41010J		10		TB4101X	B014	1A	ALL	
2202B	22	PB		KB	2-9	24-41-11	D41010J		8		TB4101X	B013	1A	YC051-YC055	
2202B	22	PB		KB	3-1	24-41-11	D41010J		8		TB4101X	B013	1A	YC056-YR328	
2202R	22	PB		KB	0-0	24-41-11	D41010J		7		TB4101X	A013	1A	ALL	
3001B	24	Y3		WA	2-1	21-31-11	D40554J		B05		D40242J	A05		YC051-YC055	
3001B	24	Y3		WA	2-0	21-31-11	D40554J		B05		D40242J	A05		YC056-YR328	
3001R	24	Y3		WA	0-0	21-31-11	D40554J		A05		D40242J	A04		ALL	
3001Y	24	Y3		WA	0-0	21-31-11	D40554J		A06		D40242J	A06		ALL	
3001Z				WA	0-0	21-31-11	D40554J	PERG	1F		D40242J	PERG	1F	ALL	
W0411	286A0411				E4-1 ELCTRONIC SHELF										
0001	22	G5			2-10	23-51-11	D02501B		K04		D04155J	A02		YC051-YC055	
0001	22	G5			2-7	23-51-11	D02501B		K04		D04155J	A02		YC056-YD157, YL951-YR328	
0001	22	PA			2-7	23-51-11	D02501B		K04		D04155J	A02		YD158-YD170	
0002	22	G5			2-10	23-51-11	D02501B		K05		D04155J	A03		YC051-YC055	
0002	22	G5			2-7	23-51-11	D02501B		K05		D04155J	A03		YC056-YD157, YL951-YR328	
0002	22	PA			2-7	23-51-11	D02501B		K05		D04155J	A03		YD158-YD170	
0003	22	G5			2-10	23-51-11	D02501B		K03		D04155J	B03		YC051-YC055	
0003	22	G5			2-7	23-51-11	D02501B		K03		D04155J	B03		YC056-YD157, YL951-YR328	
0003	22	PA			2-7	23-51-11	D02501B		K03		D04155J	B03		YD158-YD170	
0004	22	G5			2-10	23-51-11	D02501B		J05		D04155J	A04		YC051-YC055	
0004	22	G5			2-7	23-51-11	D02501B		J05		D04155J	A04		YC056-YD157, YL951-YR328	
0004	22	PA			2-7	23-51-11	D02501B		J05		D04155J	A04		YD158-YD170	
0005	24	G6			0-7	23-51-51	D02501B		C09		D02501B	A02		ALL	
0007	22	G5			2-9	23-51-21	D02501B		K09		D04331J	A02		YC051-YC055	
0007	22	G5			2-6	23-51-21	D02501B		K09		D04331J	A02		YC056-YR328	

WIRE LIST

D280A108

91-21-11

Section W0410

Page 28

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411	286A0411				E4-1 ELCTRONIC SHELF (continued)											
0008	22		G5		2-9	23-51-21		D02501B		K10		D04331J		A03		YC051-YC055
0008	22		G5		2-6	23-51-21		D02501B		K10		D04331J		A03		YC056-YR328
0009	22		G5		2-9	23-51-21		D02501B		K08		D04331J		B03		YC051-YC055
0009	22		G5		2-6	23-51-21		D02501B		K08		D04331J		B03		YC056-YR328
0010	22		G5		2-9	23-51-21		D02501B		J07		D04331J		A04		YC051-YC055
0010	22		G5		2-6	23-51-21		D02501B		J07		D04331J		A04		YC056-YR328
0012	22		G5		2-7	23-51-31		D02501B		K14		D04153J		A02		YC051-YC055
0012	22		G5		2-5	23-51-31		D02501B		K14		D04153J		A02		YC056-YR328
0013	22		G5		2-7	23-51-31		D02501B		K15		D04153J		A03		YC051-YC055
0013	22		G5		2-5	23-51-31		D02501B		K15		D04153J		A03		YC056-YR328
0014	22		G5		2-7	23-51-31		D02501B		K13		D04153J		B03		YC051-YC055
0014	22		G5		2-5	23-51-31		D02501B		K13		D04153J		B03		YC056-YR328
0015	22		G5		2-7	23-51-31		D02501B		J09		D04153J		A04		YC051-YC055
0015	22		G5		2-5	23-51-31		D02501B		J09		D04153J		A04		YC056-YR328
0017	22		CQ		3-3	23-51-51		D02501B		G01		TB4101X		A025	1A	ALL
0018	22		CQ		3-3	23-51-51		D02501B		E01		TB4101X		A026	1A	ALL
0019	22		CQ		3-0	23-51-51		D02501B		F01		TB4101X		A029	1A	YC051-YC055
0019	22		CQ		2-11	23-51-51		D02501B		F01		TB4101X		A029	1A	YC056-YR328
001CO				CU	0-0	23-32-21		D02813C		= C2		D02819		= C1		YL951-YL954, YN231-YN260
001CO				MA	0-0	23-32-21		D02813C		= C2		D02819		= C1		YL955-YL999
001CX			0F	CU	1-2	23-32-21		D02813C		A2	DN	D02819		= A1		YL951-YL954, YN231-YN260
001CX			0F	MA	1-2	23-32-21		D02813C		A2	DN	D02819		= A1		YL955-YL999
0020	22		CQ		3-2	23-51-51		D02501B		H01		TB4101Y		B023	1A	ALL
0021	22		G5		2-10	23-51-51		D02501B		A15		GD04102		DC..	1A	ALL
0022	22		G5		2-10	23-51-51		D02501B		F02		GD04102		DC..	1A	ALL
0023	22		G5		2-10	23-51-51		D02501B		E02		GD04102		DC..	1A	ALL
0024	22		G5		2-10	23-51-51		D02501B		G02		GD04102		DC..	1A	ALL
0025	22		G5		2-10	23-51-51		D02501B		H02		GD04102		DC..	1A	ALL
0026	22		G5		2-10	23-51-51		D02501B		C01		GD04102		DC..	1A	ALL
0027	22		G5		2-11	23-51-51		D02501A		J09		GD04102		DC..	1A	ALL
0028	24		G6		0-7	23-51-51		D02501A		G10		D02501A		G11		ALL
0029	24		G6		0-7	23-51-51		D02501A		A12		D02501A		C13		ALL
0030	24		G6		0-7	23-51-51		D02501A		J11		D02501A		H11		ALL
0031	22		G5		3-7	23-51-51		D02501A		H13		TB4101X		A009	1A	ALL
0032	22		G5		3-7	23-51-51		D02501A		D12		TB4101X		B009	1A	ALL
0035	24		PK		2-10	73-22-31		D02501A		K05		TB4101Y		A051	1A	ALL
0036	24		PK		2-6	73-22-31		D02501A		F05		TB4101Y		A053	1A	ALL

WIRE LIST

D280A108

91-21-11

Section W0410

Page 29

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411		286A0411			E4-1 ELCTRONIC SHELF (continued)											
0037		22		PA		2-9	23-31-02	D02501A	K03			D08123J	A01			YC051-YC055
0037		22		PA		2-7	23-31-02	D02501A	K03			D08123J	A01			YC056-YR328
0038		24		PK		2-6	23-31-02	D08123J	B01			TB4101Y	A005	1A		YC051-YC055
0038		24		PK		2-8	23-31-02	D08123J	B01			TB4101Y	A005	1A		YC056-YR328
0039		22		PA		0-7	23-31-02	D02501A	K02			D02501A	H05			ALL
0040		22		PA		0-7	23-31-02	D02501A	J05			D02501A	G02			ALL
0041		24		PK		3-7	23-31-02	D02501A	F02			TB4101Y	A005	1A		ALL
0042		24		PK		2-9	23-31-04	D02501A	G01			D08123J	A03			YC051-YC055
0042		24		PK		2-7	23-31-04	D02501A	G01			D08123J	A03			YC056-YR328
0043		22		PA		2-11	23-31-04	D02501A	B01			GD04102	DC..	1A		ALL
0044		24		PK		2-9	23-31-04	D02501A	F01			D08123J	B02			YC051-YC055
0044		24		PK		2-7	23-31-04	D02501A	F01			D08123J	B02			YC056-YR328
0045		24		PK		2-9	23-31-04	D02501A	E01			D08123J	B03			YC051-YC055
0045		24		PK		2-7	23-31-04	D02501A	E01			D08123J	B03			YC056-YR328
0046		24		PK		3-7	23-31-04	D02501A	A01			TB4101Y	A005	1A		ALL
0047		24		PK		2-9	23-31-04	D02501A	H01			D08123J	A02			YC051-YC055
0047		24		PK		2-7	23-31-04	D02501A	H01			D08123J	A02			YC056-YR328
0048		22		PA		1-11	23-71-01	D04371J	A02			TB4101X	A030	1A		YC051-YC055
0048		22		PA		2-0	23-71-01	D04371J	A02			TB4101X	A030	1A		YC056-YR328
0049		22		G5		2-7	23-22-11	D02555C	2			TB4101X	B026	1A		YC051-YD157
0049		22		G5		2-10	23-22-11	D02555C	2			TB4101X	B026	1A		YD158-YR328
0050		22		G5		2-3	23-22-11	D02555C	3			GD04102	DC..	1A		YC051-YD157
0050		22		G5		2-5	23-22-11	D02555C	3			GD04102	DC..	1A		YD158-YR328
0051		22		G5		2-3	23-22-11	D02555C	4			GD04102	DC..	1A		YC051-YD157
0051		22		G5		2-5	23-22-11	D02555C	4			GD04102	DC..	1A		YD158-YN235
0051		22		G5		2-5	23-22-11	D02555C	4			GD04102	ST..	1A		YN236-YR328
0052		22		PA		2-4	23-71-01	D04157J	A01			TB4101X	B030	1A		YC051-YC055
0052		22		PA		2-7	23-71-01	D04157J	A01			TB4101X	B030	1A		YC056-YR328
0053		22		G5		2-9	23-22-11	D02555B	B04			TB4101X	A027	1A		YC051-YD157
0053		22		G5		3-0	23-22-11	D02555B	B04			TB4101X	A027	1A		YD158-YR328
0054		22		G5		2-4	23-22-11	D02555B	A04			GD04102	DC..	1A		YC051-YD157
0054		22		G5		2-7	23-22-11	D02555B	A04			GD04102	DC..	1A		YD158-YR328
0055		22		G5		3-4	23-22-11	D02501A	K12			TB4101X	A028	1A		ALL
0056		22		G5		2-11	23-22-11	D02501A	J12			D04285J	A01			YC051-YC055
0056		22		G5		2-8	23-22-11	D02501A	J12			D04285J	A01			YC056-YD157, YL951-YR328
0056		22		PA		2-8	23-22-11	D02501A	J12			D04285J	A01			YD158-YD170
0057		22		G5		2-4	23-22-11	D02555B	A08			GD04102	DC..	1A		YC051-YD157
0057		22		PA		2-7	23-22-11	D02555B	A08			GD04102	DC..	1A		YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0410

Page 30

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To							
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411	286A0411			E4-1 ELCTRONIC SHELF (continued)											
0057	22		G5		2-7	23-22-11	D02555B	A08			GD04102	DC..	1A		YL951-YR328
0058	24		G6		1-9	23-22-11	D02555B	D06			SM00044		W		YC051-YD157
0058	24		PK		1-8	23-22-11	D02555B	D06			D04721J	A01			YD158-YD170
0058	24		G6		1-8	23-22-11	D02555B	D06			D04721J	A01			YL951-YR328
0059	24		G6		1-11	23-22-11	D02555B	A07			TB4101Y	B059	1A		YC051-YD157
0059	24		PK		1-8	23-22-11	D02555B	A07			D04721J	A02			YD158-YD170
0059	24		G6		1-8	23-22-11	D02555B	A07			D04721J	A02			YL951-YR328
0060	24		G6		1-9	23-22-11	D02555B	B07			SM00217		W		YC051-YD157
0060	24		PK		2-11	23-22-11	D04721J	A03			TB4101Y	B003	1A		YD158-YD170
0060	24		G6		2-11	23-22-11	D04721J	A03			TB4101Y	B003	1A		YL951-YL999
0060	24		G6		2-11	23-22-11	TB4101Y	B003	1A		D04721J	A03			YN231-YR328
0061	24		G6		1-1	23-22-11	D02555B	C07			SM00210		W		YC051-YC055
0061	24		G6		0-7	23-22-11	D02555B	C07			SM00210		W		YC056-YD157
0061	24		PK		1-8	23-22-11	D02555B	C07			D04721J	A04			YD158-YD170
0061	24		G6		1-8	23-22-11	D02555B	C07			D04721J	A04			YL951-YR328
0062	24		PK		1-8	23-22-11	D04721J	A05			D02555B	D07			YD158-YD170
0062	24		G6		1-8	23-22-11	D02555B	D07			D04721J	A05			YL951-YR328
0063	24		G6		3-0	23-22-11	D02555B	A01			TB4101Y	B005	1A		YC051-YD157
0063	24		PK		1-8	23-22-11	D02555B	A01			D04721J	A06			YD158-YD170
0063	24		G6		1-8	23-22-11	D02555B	A01			D04721J	A06			YL951-YR328
0064	24		G6		2-1	23-22-11	D02555B	B01			TB4101Y	B079	1A		YC051-YD157
0064	24		PK		1-8	23-22-11	D02555B	B01			D04721J	A07			YD158-YD170
0064	24		G6		1-8	23-22-11	D02555B	B01			D04721J	A07			YL951-YR328
0065	24		G6		1-9	23-22-11	D02555B	C01			SM00046		W		YC051-YD157
0065	24		PK		1-7	23-22-11	D04721J	A08			SM00046		W		YD158-YD170
0065	24		G6		1-8	23-22-11	SM00046		W		D04721J	A08			YL951-YR328
0066	24		G6		2-1	23-22-11	D02555B	D01			TB4101Y	A079	1A		YC051-YD157
0066	24		PK		1-8	23-22-11	D02555B	D01			D04721J	A09			YD158-YD170
0066	24		G6		1-8	23-22-11	D02555B	D01			D04721J	A09			YL951-YR328
0067	24		PK		1-8	23-22-11	D04721J	A10			D02555B	A02			YD158-YD170
0067	24		G6		1-8	23-22-11	D02555B	A02			D04721J	A10			YL951-YR328
0068	22		PA		0-7	23-51-11	D04155J	A13			D04155J	B13			YC051-YD157
0069	22		PA		0-7	23-51-21	D04331J	A17			D04331J	B13			YC051-YD157
0070	24		B6		2-5	23-41-11	D02501B	D06			D04157J	B09			YC051-YC055
0070	24		B6		2-2	23-41-11	D02501B	D06			D04157J	B09			YC056-YR328
0071	24		B6		2-11	23-41-11	TB4101Y	B001	1A		D04157J	A09			YC051-YC055
0071	24		B6		3-1	23-41-11	TB4101Y	B001	1A		D04157J	A09			YC056-YR328
0072	22		CQ		2-5	23-42-12	TB4101Y	B023	1A		D04287J	A01			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W0410

Page 31

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411	286A0411				E4-1 ELCTRONIC SHELF (continued)										
0072	22		CQ		2-7	23-42-12	TB4101Y	B023	1A		D04287J	A01			YC056-YN260, YR315-YR328
0073	22		PA		2-8	23-12-11	TB4101Y	B005	1A		D04287J	B01			YC051-YC055
0073	22		PA		2-10	23-12-11	TB4101Y	B005	1A		D04287J	B01			YC056-YD157
0073	22		PA		2-9	23-12-11	D02501A	H06			D04287J	B01			YD158-YD170
0073	22		CQ		2-9	23-12-11	D02501A	H06			D04287J	B01			YL951-YR328
0074	24		B6		1-5	23-12-11	D04287J	A02			SM00022		W		YC051-YC055
0074	24		B6		1-7	23-12-11	D04287J	A02			SM00022		W		YC056-YD170
0074	24		B6		1-6	23-12-11	D04287J	A02			SM00022		W		YL951-YR328
0075	22		G5		2-8	23-12-21	TB4101Y	B079	1A		D04285J	A02			YC051-YC055
0075	22		G5		2-5	23-12-21	TB4101Y	B079	1A		D04285J	A02			YC056-YD157
0075	22		PA		2-8	23-12-21	D02501A	A09			D04285J	A02			YD158-YD170
0075	22		G5		2-8	23-12-21	D02501A	A09			D04285J	A02			YL951-YR328
0077	22		PA		2-0	23-71-01	D04157J	B01			D04371J	B01			ALL
0078	24		PK		2-0	23-71-01	D04157J	A02			D04371J	B03			ALL
0079	24		PK		2-0	23-71-01	D04157J	B02			D04371J	A03			ALL
0080	24		PK		2-0	23-71-01	D04157J	A03			D04371J	B04			ALL
0081	24		PK		2-0	23-71-01	D04157J	B03			D04371J	A04			YC051-YL959, YN231-YN235
0082	24		PK		2-0	23-71-01	D04157J	A04			D04371J	B02			ALL
0083	22		PA		2-0	23-71-01	D04157J	B04			D04371J	A05			ALL
0084	22		G5		3-7	22-14-11	D02501A	F10			TB4101X	A012	1A		ALL
0086	22		PA		1-4	23-12-11	D04285J	B01			SM00022		W		YC051-YC055
0086	22		PA		1-6	23-12-11	D04285J	B01			SM00022		W		YC056-YD157
0087	22		G5		1-3	23-12-31	D08123J	B20			SM00022		W		YC051-YC055
0087	22		G5		1-5	23-12-31	D08123J	B20			SM00022		W		YC056-YD157
0087	22		PA		1-0	23-12-31	D04289J	B07			SM00022		W		YD158-YD170
0087	22		PA		1-1	23-12-31	D04289J	B07			SM00022		W		YL951-YR328
0088	22		G5		1-3	23-12-31	SM00046		W		D08123J	B18			YC051-YC055
0088	22		G5		1-5	23-12-31	SM00046		W		D08123J	B18			YC056-YD157
0088	22		G5		2-9	23-12-31	D02501A	F07			D04289J	B08			YD158-YD170, YN501
0088	22		PA		2-9	23-12-31	D04289J	B08			D02501A	F07			YL951-YN260, YR301-YR328
0089	22		PA		2-10	23-27-31	D10727A	G09			D02501A	H12			YD158-YN235
0089	22		PA		2-10	23-27-31	D10727A	G09	VP		D02501A	H12			YN236-YR328
008CO				MH	0-0	23-32-21	D02821	= C1			D40151J	B06			YL951-YN260
008CX			OF	MH	1-3	23-32-21	D02821	= A1			D40151J	A06			YL951-YN260
0092	24		PK		3-8	23-22-11	D02501A	D13			TB4101Y	B003	1A		YD158-YD170, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0410

Page 32

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411	286A0411				E4-1 ELCTRONIC SHELF (continued)										
0092	24		PK		3-7	23-22-11	D02501A	D13			TB4101Y	B003	1A		YL951-YN260
0093	24		PK		3-8	23-22-11	D02501A	G13			TB4101Y	B003	1A		YD158-YD170, YN501-YR328
0093	24		PK		3-7	23-22-11	D02501A	G13			TB4101Y	B003	1A		YL951-YN260
0094	24		PK		2-2	23-22-11	D02501A	G12			D02555B	B07			YD158-YR328
0095	24		PK		2-0	23-22-11	D02555B	C01			SM00046		W		YD158-YD170
0095	24		PK		0-7	23-22-11	D02555B	C01			SM00046		W		YL951-YR328
0096	22		G5		1-11	23-27-11	D08123J	A17			TB4101Z	B045	1A		YC051-YC053
0096	22		G5		1-3	23-27-11	D08123J	A17			SM00046		W		YC054-YC055
0096	22		G5		1-5	23-27-11	D08123J	A17			SM00046		W		YC056-YD157
0097	22		PA		2-6	23-27-11	TB4101Y	B003	1A		D08123J	B17			YC051-YC055
0097	22		PA		2-8	23-27-11	TB4101Y	B003	1A		D08123J	B17			YC056-YD157
0098	22		G5		2-9	23-27-11	D02501A	H12			D08123J	A18			YC051-YC055
0098	22		G5		2-7	23-27-11	D02501A	H12			D08123J	A18			YC056-YD157
0099	22		PA		2-3	23-27-31	D10727A	H09			D04007J	B01			YD158-YD170, YL955-YL999, YN236-YR328
0099	22		PA		1-6	23-27-31	D10727A	H09			SM00204		W		YL951-YL954, YN231-YN235
0100	24		G6		2-6	23-22-11	D02555B	A10			M01995	1	1A		YC051-YD157
0100	24		G6		2-4	23-22-11	D02555B	A10			M01995	1	1A		YD158-YR328
0101	24		G6		2-6	23-22-11	D02555B	B10			M01995	2	1A		YC051-YD157
0101	24		G6		2-4	23-22-11	D02555B	B10			M01995	2	1A		YD158-YR328
0102	24		G6		2-6	23-22-11	D02555B	C10			M01995	3	1A		YC051-YD157
0102	24		G6		2-4	23-22-11	D02555B	C10			M01995	3	1A		YD158-YR328
0103	24		G6		2-6	23-22-11	D02555B	D10			M01995	4	1A		YC051-YD157
0103	24		G6		2-4	23-22-11	D02555B	D10			M01995	4	1A		YD158-YR328
0104	24		G6		2-6	23-22-11	D02555B	A11			M01995	5	1A		YC051-YD157
0104	24		G6		2-4	23-22-11	D02555B	A11			M01995	5	1A		YD158-YR328
0105	24		G6		2-6	23-22-11	D02555B	B11			M01995	6	1A		YC051-YD157
0105	24		G6		2-4	23-22-11	D02555B	B11			M01995	6	1A		YD158-YR328
0106	24		G6		2-6	23-22-11	D02555B	C11			M01995	7	1A		YC051-YD157
0106	24		G6		2-4	23-22-11	D02555B	C11			M01995	7	1A		YD158-YR328
0107	24		G6		2-6	23-22-11	D02555B	D11			M01995	8	1A		YC051-YD157
0107	24		G6		2-4	23-22-11	D02555B	D11			M01995	8	1A		YD158-YR328
0108	24		G6		2-6	23-22-11	D02555B	A13			M01995	9	1A		YC051-YD157
0108	24		G6		2-4	23-22-11	D02555B	A13			M01995	9	1A		YD158-YR328
0109	24		G6		2-6	23-22-11	D02555B	B13			M01995	10	1A		YC051-YD157
0109	24		G6		2-4	23-22-11	D02555B	B13			M01995	10	1A		YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0410

Page 33

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type
W0411	286A0411				E4-1 ELCTRONIC SHELF (continued)										
0110	24		G6	2-6	23-22-11	D02555B		C13			M01995	11	1A		YC051-YD157
0110	24		G6	2-4	23-22-11	D02555B		C13			M01995	11	1A		YD158-YR328
0111	24		G6	2-6	23-22-11	D02555B		D13			M01995	12	1A		YC051-YD157
0111	24		G6	2-4	23-22-11	D02555B		D13			M01995	12	1A		YD158-YR328
0112	24		G6	2-6	23-22-11	D02555B		A15			M01995	13	1A		YC051-YD157
0112	24		G6	2-4	23-22-11	D02555B		A15			M01995	13	1A		YD158-YR328
0113	24		G6	2-6	23-22-11	D02555B		B15			M01995	14	1A		YC051-YD157
0113	24		G6	2-4	23-22-11	D02555B		B15			M01995	14	1A		YD158-YR328
0114	24		G6	2-6	23-22-11	D02555B		C15			M01995	15	1A		YC051-YD157
0114	24		G6	2-4	23-22-11	D02555B		C15			M01995	15	1A		YD158-YR328
0115	24		G6	2-6	23-22-11	D02555B		D15			M01995	16	1A		YC051-YD157
0115	24		G6	2-4	23-22-11	D02555B		D15			M01995	16	1A		YD158-YR328
0116	24		G6	2-6	23-22-11	D02555B		C09			M01995	17	1A		YC051-YD157
0116	24		G6	2-4	23-22-11	D02555B		C09			M01995	17	1A		YD158-YR328
0117	24		G6	2-6	23-22-11	D02555B		D09			M01995	18	1A		YC051-YD157
0117	24		G6	2-4	23-22-11	D02555B		D09			M01995	18	1A		YD158-YR328
0118	24		G6	2-6	23-22-11	D02555B		B09			M01995	25	1A		YC051-YD157
0118	24		G6	2-4	23-22-11	D02555B		B09			M01995	25	1A		YD158-YR328
0119	24		G6	2-6	31-31-17	D08123J		A10			TB4101X	A011	1A		YC051-YC055
0119	24		G6	2-8	31-31-17	D08123J		A10			TB4101X	A011	1A		YC056-YD170
0119	24		PK	2-8	31-31-17	D08123J		A10			TB4101X	A011	1A		YL951-YR328
0120	22		PA	3-3	23-29-11	D44145J		A02			TB4101Y	CAP	Y		YC051-YC055
0120	22		PA	2-10	23-29-11	D44145J		A02			TB4101Y	CAP	Y		YC056-YD157
0121	22		PA	2-5	23-29-11	TB4101Y		A079	1A		D02501A	C10			YC051-YD157
0122	22		PA	2-6	23-29-11	D08123J		A13			TB4101Y	A079	1A		YC051-YC055
0122	22		PA	2-4	23-29-11	D08123J		A13			TB4101Y	A079	1A		YC056-YD157
0123	24		G6	1-2	23-22-11	D04153J		A13			SM00217		W		YC051-YC055
0123	24		G6	1-4	23-22-11	D04153J		A13			SM00217		W		YC056-YD157
0124	24		G6	1-8	23-22-11	D04153J		A12			SM00210		W		YC051-YC055
0124	24		G6	1-11	23-22-11	D04153J		A12			SM00210		W		YC056-YD157
0125	24		G6	1-4	23-22-11	D04155J		A15			SM00044		W		YC051-YC055
0125	24		G6	1-7	23-22-11	D04155J		A15			SM00044		W		YC056-YD157
0126	24		G6	2-6	23-22-11	D04155J		A16			TB4101Y	B059	1A		YC051-YC055
0126	24		G6	2-3	23-22-11	D04155J		A16			TB4101Y	B059	1A		YC056-YD157
0127	24		G6	1-4	23-22-11	D04155J		A17			SM00217		W		YC051-YC055
0127	24		G6	1-7	23-22-11	D04155J		A17			SM00217		W		YC056-YD157
0128	24		G6	1-10	23-22-11	D04155J		A18			SM00210		W		YC051-YC055
0128	24		G6	2-2	23-22-11	D04155J		A18			SM00210		W		YC056-YD157
0130	24		G6	1-9	23-22-11	D04331J		A13			SM00210		W		YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W0410

Page 34

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411	286A0411				E4-1 ELCTRONIC SHELF (continued)										
0130	24		G6		2-1	23-22-11	D04331J	A13			SM00210		W		YC056-YD157
0131	24		G6		1-3	23-22-11	D04331J	A14			SM00217		W		YC051-YC055
0131	24		G6		1-5	23-22-11	D04331J	A14			SM00217		W		YC056-YD157
0132	24		G6		2-4	23-22-11	D04331J	A15			TB4101Y	B059	1A		YC051-YC055
0132	24		G6		2-2	23-22-11	D04331J	A15			TB4101Y	B059	1A		YC056-YD157
0132	22		PA		2-7	23-11-11	D02501A	C10			D08123J	B15			YL951-YR328
0133	24		G6		1-3	23-22-11	D04331J	A16			SM00044		W		YC051-YC055
0133	24		G6		1-5	23-22-11	D04331J	A16			SM00044		W		YC056-YD157
0159	24		PK		2-1	23-27-31	D10727A	D11			D04155J	B14			YD158-YR328
0174	22		PA		2-8	23-11-21	D02501A	J07			D04285J	A13			YD158-YD170, YN501-YR328
0179	24		PK		1-6	23-12-21	D04285J	B01			SM00022		W		YD158-YD170
0179	24		PK		1-5	23-12-21	D04285J	B01			SM00022		W		YL951-YR328
0185	22		PA		2-10	23-27-11	D04153J	CAP	Y		TB4101	CAP	Y		YC051-YC053
0185	22		PA		2-6	23-27-11	D04153J	A14			TB4101Y	B003	1A		YC054-YC055
0185	22		PA		2-8	23-27-11	D04153J	A14			TB4101Y	B003	1A		YC056-YD157
0187	22		PA		3-1	23-27-11	D04155J	CAP	Y		TB4101	CAP	Y		YC051-YC053
0187	22		PA		2-8	23-27-11	D04155J	A20			TB4101Y	B003	1A		YC054-YC055
0187	22		PA		2-10	23-27-11	D04155J	A20			TB4101Y	B003	1A		YC056-YD157
0189	22		PA		2-11	23-27-11	D04331J	CAP	Y		TB4101	CAP	Y		YC051-YC053
0189	22		PA		2-7	23-27-11	D04331J	A19			TB4101Y	B003	1A		YC054-YC055
0189	22		PA		2-9	23-27-11	D04331J	A19			TB4101Y	B003	1A		YC056-YD157
0193	24		PK		1-11	23-43-11	D04153J	A16			TB4101Y	A035	1A		YC051-YC055
0193	24		PK		2-1	23-43-11	D04153J	A16			TB4101Y	A035	1A		YC056-YD157
0194	24		PK		2-1	23-43-11	D04155J	B15			TB4101Y	A035	1A		YC051-YC055
0194	24		PK		2-3	23-43-11	D04155J	B15			TB4101Y	A035	1A		YC056-YD157
0196	24		PK		2-0	23-43-11	D04331J	B14			TB4101Y	A035	1A		YC051-YC055
0196	24		PK		2-2	23-43-11	D04331J	B14			TB4101Y	A035	1A		YC056-YD157
0199	22		PA		2-3	23-42-11	TB4101Y	A081	1A		D02501A	E09			YC051-YD157
0200	22		PA		2-11	23-43-11	GD04102	DC..	1A		D02501A	D09			YC051-YD157
0203	22		PA		2-11	23-43-11	GD04102	DC..	1A		D02501A	C08			YC051-YD157
0204	24		PK		3-0	23-43-11	TB4101Y	A035	1A		D02501A	A08			YC051-YD157
0206	22		PA		2-8	23-11-21	D02501A	J07			D04285J	A13			YL951-YN260
0207	24		G6		2-9	31-31-17	D04285J	B17			TB4101X	B012	1A		YD158-YR328
0263	24		PK		3-0	23-15-12	D02501A	A11			D41101J	B06			YC051-YD157
0264	24		PK		3-0	23-15-12	D02501A	H08			D41101J	B05			YC051-YD157
0266	24		PK		1-2	23-15-15	D04153J	B14			SM00193		W		YC051-YC055
0266	24		PK		1-4	23-15-15	D04153J	B14			SM00193		W		YC056-YD157
0267	24		PK		1-2	23-15-15	D04153J	B16			SM00191		W		YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W0410

Page 35

Nov 12/2012

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411		286A0411				E4-1 ELCTRONIC SHELF (continued)									
	0267	24	PK		1-4	23-15-15	D04153J	B16			SM00191		W		YC056-YD157
	0268	24	PK		1-2	23-15-15	D04153J	B12			SM00192		W		YC051-YC055
	0268	24	PK		1-4	23-15-15	D04153J	B12			SM00192		W		YC056-YD157
	0269	24	PK		1-2	23-15-15	D04153J	B10			SM00190		W		YC051-YC055
	0269	24	PK		1-4	23-15-15	D04153J	B10			SM00190		W		YC056-YD157
	0270	24	PK		1-4	23-15-15	D04155J	B17			SM00190		W		YC051-YC055
	0270	24	PK		1-7	23-15-15	D04155J	B17			SM00190		W		YC056-YD157
	0271	24	PK		1-4	23-15-15	D04155J	A14			SM00192		W		YC051-YC055
	0271	24	PK		1-7	23-15-15	D04155J	A14			SM00192		W		YC056-YD157
	0272	24	PK		1-4	23-15-15	D04155J	B20			SM00191		W		YC051-YC055
	0272	24	PK		1-7	23-15-15	D04155J	B20			SM00191		W		YC056-YD157
	0273	24	PK		1-4	23-15-15	D04155J	B14			SM00193		W		YC051-YC055
	0273	24	PK		1-7	23-15-15	D04155J	B14			SM00193		W		YC056-YD157
	0275	24	PK		1-3	23-15-15	D04331J	B16			SM00190		W		YC051-YC055
	0275	24	PK		1-5	23-15-15	D04331J	B16			SM00190		W		YC056-YD157
	0276	24	PK		1-3	23-15-15	D04331J	B18			SM00192		W		YC051-YC055
	0276	24	PK		1-5	23-15-15	D04331J	B18			SM00192		W		YC056-YD157
	0277	24	PK		1-3	23-15-15	D04331J	B17			SM00191		W		YC051-YC055
	0277	24	PK		1-5	23-15-15	D04331J	B17			SM00191		W		YC056-YD157
	0278	24	PK		1-3	23-15-15	D04331J	B19			SM00193		W		YC051-YC055
	0278	24	PK		1-5	23-15-15	D04331J	B19			SM00193		W		YC056-YD157
	0281	24	PK		1-2	23-15-15	SM00190		W		D41101J	B01			YC051-YC055
	0281	24	PK		1-3	23-15-15	SM00190		W		D41101J	B01			YC056-YD157
	0282	24	PK		1-2	23-15-15	SM00192		W		D41101J	B02			YC051-YC055
	0282	24	PK		1-3	23-15-15	SM00192		W		D41101J	B02			YC056-YD157
	0284	24	PK		1-2	23-15-15	SM00191		W		D41101J	B03			YC051-YC055
	0284	24	PK		1-3	23-15-15	SM00191		W		D41101J	B03			YC056-YD157
	0285	24	PK		1-2	23-15-15	SM00193		W		D41101J	B04			YC051-YC055
	0285	24	PK		1-3	23-15-15	SM00193		W		D41101J	B04			YC056-YD157
	0287	22	G5		3-7	23-12-11	D02501A	H06			TB4101Y	B005	1A		YC051-YD157
	0289	22	G5		2-5	23-12-21	D02501A	A09			TB4101Y	B079	1A		YC051-YD157
	0290	22	G5		2-4	23-12-31	D02501A	F07			SM00046		W		YC051-YD157
	0292	22	PA		2-1	23-27-31	D04115J	B17			D10727C	1			YD158-YD170
	0292	22	PA		2-1	23-27-31	D10727C		1		D04115J	B17			YL951-YR328
	0293	20	PA		1-8	23-27-31	D10727C		7		GD04103	AC..	1A		YD158-YR328
	0294	20	PA		1-8	23-27-31	D10727C		8		GD04103	AC..	1A		YD158-YL954, YN231-YN235
	0294	20	PA		1-8	23-27-31	D10727C		8		GD04103	ST..	1A		YL955-YL999, YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W0410

Page 36

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411	286A0411				E4-1 ELCTRONIC SHELF (continued)										
0296	22		PA		1-4	23-27-31	D10727B	C09			SM00046		W		YD158-YD170
0296	22		PA		2-5	23-27-31	D10727B	C09			SM00046		W		YL951-YR328
0297	22		PA		2-0	23-27-31	D10727B	G09			GD04102	DC..	1A		YD158-YN235
0297	22		PA		2-0	23-27-31	D10727B	G09	VP		GD04102	DC..	1A		YN236-YR328
0298	22		PA		2-9	23-27-31	D10727B	F09			D02501A	E13			YD158-YN235
0298	22		PA		2-9	23-27-31	D10727B	F09	VP		D02501A	E13			YN236-YR328
0300	22		PA		2-2	23-27-38	D04117J	A01			D10727A	A15			YD158-YR328
0301	22		PA		2-2	23-27-38	D04117J	B01			D10727A	B15			YD158-YR328
0302	22		PA		2-2	23-27-38	D04117J	A02			D10727A	J15			YD158-YR328
0303	22		PA		2-2	23-27-38	D04117J	B02			D10727A	C15			YD158-YR328
0304	22		PA		2-2	23-27-38	D04117J	A03			D10727A	G15			YD158-YR328
0305	22		PA		2-2	23-27-38	D04117J	B03			D10727A	H15			YD158-YR328
0306	24		PK		2-3	23-27-39	D04115J	A17			D10727A	E06			YD158-YD170
0306	24		PK		2-3	23-27-39	D10727A	E06			D04115J	A17			YL951-YR328
0307	22		PA		2-7	23-11-11	D02501A	C10			D08123J	B15			YD158-YD170
0309	24		G6		1-2	23-22-11	D04153J	A09			SM00044		W		YC051-YC055
0309	24		G6		1-4	23-22-11	D04153J	A09			SM00044		W		YC056-YD157
0310	24		G6		2-3	23-22-11	D04153J	A10			TB4101Y	B059	1A		YC051-YC055
0310	24		G6		2-1	23-22-11	D04153J	A10			TB4101Y	B059	1A		YC056-YD157
0313	20		PA		1-9	23-32-21	D02813C	CAP	Y		D40151J	CAP	Y		YL951-YL967, YN231-YN235
0313	20		PA		3-2	23-32-21	D02813C	CAP	Y		SP00291		W		YL968-YL999, YN236-YN260
0314	20		PA		2-1	23-32-21	D02813C	4			GD04103	DC..	1A		YL951-YN260
0315	20		PA		0-7	23-32-21	D02813B	33			SM00215		W		YL951-YN260
0316	20		PA		0-7	23-32-21	D02813B	40			SM00215		W		YL951-YN260
0317	20		PA		0-7	23-32-21	D02813B	42			SM00215		W		YL951-YN260
0318	20		PA		2-2	23-32-21	GD04103	ST..	1A		SM00215		W		YL951-YN260
0320	20		PA		0-7	23-32-21	D02813B	36			SM00215		W		YL951-YN260
0336	22		PA		2-0	23-15-15	D04285J	A16			D41101J	A10			YC051-YC055
0336	22		PA		2-2	23-15-15	D04285J	A16			D41101J	A10			YC056-YD157
0338	22		PA		2-4	23-31-04	D02501A	J02			GD04103	DC..	1A		YD158-YR328
0342	20		PA		1-8	23-71-01	D04285J	B20			D04371J	A01			YC051-YD170
0342	20		PA		1-8	23-71-01	D04371J	A01			D04285J	B20			YL951-YR328
0344	22		PA		1-4	23-27-31	D04115J	A20			SM00204	CAP	Y		YL951-YL954, YN231-YN235
0345	22		PA		1-11	23-27-38	D10727A	K15			GD04103	DC..	1A		YD158-YD170
0345	22		PA		1-11	23-27-38	GD04103	DC..	1A		D10727A	K15			YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0410

Page 37

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411	286A0411			E4-1 ELCTRONIC SHELF (continued)											
0346	22		PA		2-3	23-27-31	D04115J	B20			D10727A	REF	VP		YL951-YL954, YN231-YN235
0347	22		PA		1-4	23-27-31	D04007J	B01			SM00204		W		YL951-YL954, YN231-YN235
0351	22		PA		1-10	23-27-11	SM00217		W		TB4101Y	B003	1A		YC051-YC053
0351	22		PA		2-5	23-27-11	SM00217		W		TB4101	CAP	Y		YC054-YD157
0352	22		G5		2-9	34-21-22	D04161J	A06			TB4101X	B029	1A		YL951-YR328
0353	22		PA		3-0	34-21-12	D04161J	B06			TB4101X	B027	1A		YL951-YR328
0357	24		PK		2-1	23-11-11	D02501B	B06			D02501A	G03			YL951-YR328
0358	24		PK		0-7	23-11-11	D02501B	C06			SM00301		W		YL951-YR328
0359	24		PK		0-7	23-11-11	D02501B	D14			SM00301		W		YL951-YR328
0360	24		PK		2-1	23-11-11	D02501A	F03			SM00301		W		YL951-YR328
0361	22		CQ		2-7	34-24-15	D11281	6			TB4101X	A016	1A		YD158
0361	20		CQ		2-7	34-24-15	D11281	6			TB4101X	A016	1A		YL951-YR328
0362	20		CQ		1-6	34-24-15	D11281	4			GD04103	DC..	1A		YD158-YR328
0363	22		CQ		1-10	34-24-15	D11281	9			D04331J	B12			YD158
0363	20		CQ		1-10	34-24-15	D11281	9			D04331J	B12			YL951-YR328
0396	08		CQ		2-3	34-24-15	D11281	2			GD04108	ST..	E		YD158-YR328
0397	22		CQ		2-7	34-24-15	D11281	3			TB4101X	B016	1A		YD158-YR328
0414	24		PK		0-7	23-11-21	D02501B	A07			SM00455		W		YL951-YR328
0415	24		PK		0-7	23-11-21	D02501B	C14			SM00455		W		YL951-YR328
0416	24		PK		2-1	23-11-21	D02501A	C02			D02501B	B07			YL951-YR328
0417	24		PK		2-1	23-11-21	D02501A	D02			SM00455		W		YL951-YR328
0472	22		PA		1-10	23-27-39	D11813	1			D10727A	H01			YD158-YD170
0472	22		PA		1-10	23-27-39	D10727A	H01			D11813	1			YL951-YL954, YN231-YN235
0473	22		PA		1-10	23-27-39	D11813	2			D10727A	E01			YD158-YD170
0473	22		PA		1-10	23-27-39	D10727A	E01			D11813	2			YL951-YL954, YN231-YN235
0474	22		PA		1-10	23-27-39	D11813	3			D10727A	C01			YD158-YD170
0474	22		PA		1-10	23-27-39	D10727A	C01			D11813	3			YL951-YL954, YN231-YN235
0475	22		PA		1-10	23-27-39	D11813	4			D10727A	K01			YD158-YD170
0475	22		PA		1-10	23-27-39	D10727A	K01			D11813	4			YL951-YL954, YN231-YN235
0476	22		PA		1-10	23-27-39	D11813	5			D10727A	D01			YD158-YD170
0476	22		PA		1-10	23-27-39	D10727A	D01			D11813	5			YL951-YL954, YN231-YN235
0477	22		PA		1-10	23-27-39	D11813	6			D10727A	A02			YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0410

Page 38

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description		From				To					
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411	286A0411			E4-1 ELCTRONIC SHELF (continued)											
0477	22		PA		1-10	23-27-39	D10727A	A02			D11813	6			YL951-YL954, YN231-YN235
0478	22		PA		1-10	23-27-39	D11813	7			D10727A	A01			YD158-YD170
0478	22		PA		1-10	23-27-39	D10727A	A01			D11813	7			YL951-YL954, YN231-YN235
0479	22		PA		1-10	23-27-39	D11813	8			D10727A	B01			YD158-YD170
0479	22		PA		1-10	23-27-39	D10727A	B01			D11813	8			YL951-YL954, YN231-YN235
0480	22		PA		1-10	23-27-39	D11813	9			D10727A	J01			YD158-YD170
0480	22		PA		1-10	23-27-39	D10727A	J01			D11813	9			YL951-YL954, YN231-YN235
0482	24		PK		1-10	31-62-42	D04285J	A17			D04331J	A20			YL951-YR328
0544	24		PK		2-3	23-27-35	D44139J	A03			D10727B	C15	VP		YN501-YR317
0545	24		PK		2-3	23-27-35	D44139J	B03			D10727B	D15	VP		YN501-YR317
2001B	24		Y2	AB	2-10	23-51-11	D02501B	C15			D04155J	B06			YC051-YC055
2001B	24		Y2	AB	2-7	23-51-11	D02501B	C15			D04155J	B06			YC056-YR328
2001R	24		Y2	AB	0-0	23-51-11	D02501B	B14			D04155J	A06			ALL
2001Z				AB	0-0	23-51-11	D02501B	DED			D04155J	PERG	1F		ALL
2002B	24		Y2	AE	2-10	23-51-11	D02501B	E14			D04155J	B07			YC051-YC055
2002B	24		Y2	AE	2-7	23-51-11	D02501B	E14			D04155J	B07			YC056-YR328
2002R	24		Y2	AE	0-0	23-51-11	D02501B	D15			D04155J	A07			ALL
2002Z				AE	0-0	23-51-11	D02501B	DED			D04155J	PERG	1F		YC051-YD157
2002Z				AE	0-0	23-51-11	D02501B	PERG	1A		D04155J	A09			YD158-YR328
2003B	24		PL	AF	2-10	23-51-11	GD04103	DC..	1A		D04155J	B10			YC051-YC055
2003B	24		PL	AF	2-7	23-51-11	GD04103	DC..	1A		D04155J	B10			YC056-YR328
2003R	24		PL	AF	0-0	23-51-11	D02501B	D08			D04155J	A10			ALL
2004B	24		Y2	AH	2-9	23-51-21	D02501B	D12			D04331J	B06			YC051-YC055
2004B	24		Y2	AH	2-6	23-51-21	D02501B	D12			D04331J	B06			YC056-YR328
2004R	24		Y2	AH	0-0	23-51-21	D02501B	D11			D04331J	A06			ALL
2004Z				AH	0-0	23-51-21	D02501B	DED			D04331J	PERG	1F		ALL
2005B	24		Y2	AK	2-9	23-51-21	D02501B	H13			D04331J	B07			YC051-YC055
2005B	24		Y2	AK	2-6	23-51-21	D02501B	H13			D04331J	B07			YC056-YR328
2005R	24		Y2	AK	0-0	23-51-21	D02501B	H12			D04331J	A07			ALL
2005Z				AK	0-0	23-51-21	D02501B	DED			D04331J	PERG	1F		YC051-YD157
2005Z				AK	0-0	23-51-21	D02501B	PERG	1A		D04331J	A09			YD158-YR328
2006B	24		PL	AL	2-9	23-51-21	GD04103	DC..	1A		D04331J	B10			YC051-YC055
2006B	24		PL	AL	2-6	23-51-21	GD04103	DC..	1A		D04331J	B10			YC056-YR328
2006R	24		PL	AL	0-0	23-51-21	D02501B	C11			D04331J	A10			ALL
2007B	24		Y2	AN	2-7	23-51-31	D02501B	D10			D04153J	B06			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W0410

Page 39

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411		286A0411					E4-1 ELCTRONIC SHELF (continued)									
2007B		24		Y2	AN	2-5	23-51-31	D02501B	D10			D04153J	B06			YC056-YR328
2007R		24		Y2	AN	0-0	23-51-31	D02501B	D09			D04153J	A06			ALL
2007Z					AN	0-0	23-51-31	D02501B	DED			D04153J	PERG	1F		ALL
2008B		24		Y2	AP	2-7	23-51-31	D02501B	F09			D04153J	B07			YC051-YC055
2008B		24		Y2	AP	2-5	23-51-31	D02501B	F09			D04153J	B07			YC056-YR328
2008R		24		Y2	AP	0-0	23-51-31	D02501B	F08			D04153J	A07			ALL
2008Z					AP	0-0	23-51-31	D02501B	DED			D04153J	PERG	1F		YC051-YD157
2008Z					AP	0-0	23-51-31	D02501B	PERG	1A		D04153J	B05			YD158-YR328
2009B		24		Y2	AQ	2-7	23-51-31	D02501B	B10			D04153J	B11			YC051-YC055
2009B		24		Y2	AQ	2-5	23-51-31	D02501B	B10			D04153J	B11			YC056-YD170
2009R		24		Y2	AQ	0-0	23-51-31	D02501B	B09			D04153J	A11			YC051-YD170
2009Z					AQ	0-0	23-51-31	D02501B	DED			D04153J	PERG	1F		YC051-YD170
2015B		24		PL	BF	2-8	23-31-02	D02501B	H07			D08123J	B04			YC051-YC055
2015B		24		PL	BF	2-6	23-31-02	D02501B	H07			D08123J	B04			YC056-YR328
2015R		24		PL	BF	0-0	23-31-02	D02501B	H06			D08123J	A04			ALL
2016B		24		PL	BG	2-8	23-31-02	D02501B	B01			D08123J	B05			YC051-YC055
2016B		24		PL	BG	2-6	23-31-02	D02501B	B01			D08123J	B05			YC056-YR328
2016R		24		PL	BG	0-0	23-31-02	D02501B	A01			D08123J	A05			ALL
2017B		24		PL	BH	2-8	23-31-02	D02501B	A06			D08123J	B06			YC051-YC055
2017B		24		PL	BH	2-6	23-31-02	D02501B	A06			D08123J	B06			YC056-YR328
2017R		24		PL	BH	0-0	23-31-02	D02501B	A04			D08123J	A06			ALL
2018B		24		PL	BI	2-8	23-31-02	D02501B	D05			D08123J	B07			YC051-YC055
2018B		24		PL	BI	2-6	23-31-02	D02501B	D05			D08123J	B07			YC056-YR328
2018R		24		PL	BI	0-0	23-31-02	D02501B	C05			D08123J	A07			ALL
2019B		22		PB	BJ	2-1	23-31-02	D04157J	B10			D08123J	B08			ALL
2019R		22		PB	BJ	0-0	23-31-02	D04157J	A10			D08123J	A08			ALL
2020B		22		PB	BK	2-11	23-31-04	TB4101Y	A007	1A		D44139J	B05			YC051-YC055
2020B		22		PB	BK	3-1	23-31-04	TB4101Y	A007	1A		D44139J	B05			YC056-YR328
2020R		22		PB	BK	0-0	23-31-04	D02501A	H02			D44139J	A05			ALL
2021B		22		PB	BL	2-11	23-31-04	TB4101Y	A007	1A		D44139J	B06			YC051-YC055
2021B		22		PB	BL	3-1	23-31-04	TB4101Y	A007	1A		D44139J	B06			YC056-YR328
2021R		22		PB	BL	0-0	23-31-04	D02501A	C01			D44139J	A06			ALL
2022B		22		PB	BM	2-9	23-31-04	TB4101Y	A007	1A		D08123J	B09			YC051-YC055
2022B		22		PB	BM	2-8	23-31-04	TB4101Y	A007	1A		D08123J	B09			YC056-YR328
2022R		22		PB	BM	0-0	23-31-04	D02501A	D01			D08123J	A09			ALL
2027B		24		Y2	AR	3-6	23-41-11	D02501B	D07			TB4101Y	A003	1A		ALL
2027R		24		Y2	AR	0-0	23-41-11	D02501B	E07			TB4101Y	A001	1A		ALL
2027Z					AR	0-0	23-41-11	D02501B	DED			TB4101Y	DED			ALL
2028B		24		PL	CK	2-0	23-71-01	D04157J	B07			D04371J	B15			ALL

WIRE LIST

D280A108

91-21-11

Section W0410

Page 40

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411	286A0411				E4-1 ELCTRONIC SHELF (continued)										
2028R	24	PL	CK		0-0	23-71-01	D04157J	A07			D04371J	A15			ALL
2029B	24	PL	CL		2-0	23-71-01	D04157J	B08			D04371J	B16			YC051-YL959, YN231-YN235
2029R	24	PL	CL		0-0	23-71-01	D04157J	A08			D04371J	A16			YC051-YL959, YN231-YN235
2030B	22	PB	CN		2-10	24-41-11	D04161J	B10			TB4101X	B013	1A		YC051-YC055
2030B	22	PB	CN		3-0	24-41-11	D04161J	B10			TB4101X	B013	1A		YC056-YR328
2030R	22	PB	CN		0-0	24-41-11	D04161J	B09			TB4101X	A013	1A		ALL
2031B	22	PB	CO		2-10	24-41-11	D04161J	A10			TB4101X	A014	1A		YC051-YC055
2031B	22	PB	CO		3-0	24-41-11	D04161J	A10			TB4101X	A014	1A		YC056-YR328
2031R	22	PB	CO		0-0	24-41-11	D04161J	A09			TB4101X	B014	1A		ALL
2068B	22	X2	BU		1-10	23-27-39	D10727A	D01			D11813	5			YL955-YL999, YN501-YR328
2068B	22	X2	FC		1-10	23-27-39	D10727A	D01			D11813	5			YN236-YN260
2068R	22	X2	BU		0-0	23-27-39	D10727A	K01			D11813	4			YL955-YL999, YN501-YR328
2068R	22	X2	FC		0-0	23-27-39	D10727A	K01			D11813	4			YN236-YN260
2068Z			BU		0-0	23-27-39	D10727A	PERG	1A		D11813			CU	YL955-YL999, YN501-YR328
2068Z			FC		0-0	23-27-39	D10727A	PERG	1A		D11813			CU	YN236-YN260
2069B	22	X2	BQ		1-10	23-27-39	D10727A	A01			D11813	7			YL955-YL999, YN501-YR328
2069B	22	X2	FD		1-10	23-27-39	D10727A	A01			D11813	7			YN236-YN260
2069R	22	X2	BQ		0-0	23-27-39	D10727A	A02			D11813	6			YL955-YL999, YN501-YR328
2069R	22	X2	FD		0-0	23-27-39	D10727A	A02			D11813	6			YN236-YN260
2069Z			BQ		0-0	23-27-39	D10727A	PERG	1A		D11813			CU	YL955-YL999, YN501-YR328
2069Z			FD		0-0	23-27-39	D10727A	PERG	1A		D11813			CU	YN236-YN260
2070B	22	X2	BR		1-10	23-27-39	D10727A	J01			D11813	9			YL955-YL999, YN501-YR328
2070B	22	X2	FE		1-10	23-27-39	D10727A	J01			D11813	9			YN236-YN260
2070R	22	X2	BR		0-0	23-27-39	D10727A	B01			D11813	8			YL955-YL999, YN501-YR328
2070R	22	X2	FE		0-0	23-27-39	D10727A	B01			D11813	8			YN236-YN260
2070Z			BR		0-0	23-27-39	D10727A	PERG	1A		D11813			CU	YL955-YL999, YN501-YR328
2070Z			FE		0-0	23-27-39	D10727A	PERG	1A		D11813			CU	YN236-YN260
2501B	24	Y2	AA		2-10	23-51-11	D02501B	K02			D04155J	B01			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W0410

Page 41

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411		286A0411				E4-1 ELCTRONIC SHELF (continued)									
	2501B	24	Y2	AA	2-7	23-51-11	D02501B	K02			D04155J	B01			YC056-YR328
	2501R	24	Y2	AA	0-0	23-51-11	D02501B	K01			D04155J	A01			ALL
	2501Z			AA	0-0	23-51-11	D02501B	PERG	1A		D04155J	B02			YC051-YD157
	2501Z			AA	0-0	23-51-11	D02501B	PERG	1A		D04155J	PERG	1F		YD158-YR328
	2502B	24	Y2	AG	2-9	23-51-21	D02501B	K07			D04331J	B01			YC051-YC055
	2502B	24	Y2	AG	2-6	23-51-21	D02501B	K07			D04331J	B01			YC056-YR328
	2502R	24	Y2	AG	0-0	23-51-21	D02501B	K06			D04331J	A01			ALL
	2502Z			AG	0-0	23-51-21	D02501B	PERG	1A		D04331J	B02			YC051-YD157
	2502Z			AG	0-0	23-51-21	D02501B	PERG	1A		D04331J	PERG	1F		YD158-YR328
	2503B	24	Y2	AM	2-7	23-51-31	D02501B	K12			D04153J	B01			YC051-YC055
	2503B	24	Y2	AM	2-5	23-51-31	D02501B	K12			D04153J	B01			YC056-YR328
	2503R	24	Y2	AM	0-0	23-51-31	D02501B	K11			D04153J	A01			ALL
	2503Z			AM	0-0	23-51-31	D02501B	PERG	1A		D04153J	B02			YC051-YD157
	2503Z			AM	0-0	23-51-31	D02501B	PERG	1A		D04153J	PERG	1F		YD158-YR328
	2504B	24	M5	AW	3-0	34-31-11	D02501A	E11			D04287J	B08			YC051-YC055
	2504B	24	M5	AW	2-9	34-31-11	D02501A	E11			D04287J	B08			YC056-YR328
	2504R	24	M5	AW	0-0	34-31-11	D02501A	E12			D04287J	A08			ALL
	2504ZI			AW	0-0	34-31-11	D02501A	PERG	1A		D04287J	B09			ALL
	2504ZO			AW	0-0	34-31-11	D02501A	PERG	1A		D04287J	PERG	1F		ALL
	2505B	24	M5	AX	2-11	34-31-21	D02501A	G09			D04285J	B07			YC051-YC055
	2505B	24	M5	AX	2-8	34-31-21	D02501A	G09			D04285J	B07			YC056-YR328
	2505R	24	M5	AX	0-0	34-31-21	D02501A	H09			D04285J	A07			ALL
	2505ZI			AX	0-0	34-31-21	D02501A	PERG	1A		D04285J	B08			ALL
	2505ZO			AX	0-0	34-31-21	D02501A	PERG	1A		D04285J	PERG	1F		ALL
	2506B	24	M5	AY	3-0	34-32-11	D02501A	A14			D04287J	B10			YC051-YC055
	2506B	24	M5	AY	2-9	34-32-11	D02501A	A14			D04287J	B10			YC056-YR328
	2506R	24	M5	AY	0-0	34-32-11	D02501A	A15			D04287J	A10			ALL
	2506ZI			AY	0-0	34-32-11	D02501A	PERG	1A		D04287J	A09			ALL
	2506ZO			AY	0-0	34-32-11	D02501A	PERG	1A		D04287J	PERG	1F		ALL
	2507B	24	M5	AZ	3-0	34-51-11	D02501A	J13			D04287J	B11			YC051-YC055
	2507B	24	M5	AZ	2-9	34-51-11	D02501A	J13			D04287J	B11			YC056-YR328
	2507R	24	M5	AZ	0-0	34-51-11	D02501A	K13			D04287J	A11			ALL
	2507ZI			AZ	0-0	34-51-11	D02501A	PERG	1A		D04287J	B12			ALL
	2507ZO			AZ	0-0	34-51-11	D02501A	PERG	1A		D04287J	PERG	1F		ALL
	2508B	24	M5	BA	2-11	34-51-21	D02501A	C15			D04285J	B09			YC051-YC055
	2508B	24	M5	BA	2-8	34-51-21	D02501A	C15			D04285J	B09			YC056-YR328
	2508R	24	M5	BA	0-0	34-51-21	D02501A	D15			D04285J	A09			ALL
	2508ZI			BA	0-0	34-51-21	D02501A	PERG	1A		D04285J	A08			ALL
	2508ZO			BA	0-0	34-51-21	D02501A	PERG	1A		D04285J	PERG	1F		ALL

WIRE LIST

D280A108

91-21-11

Section W0410

Page 42

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411	286A0411			E4-1 ELCTRONIC SHELF (continued)											
2509B	24	M5	CQ		2-5	23-22-11	D02555B	B05			D04287J	B19			YC051-YC055, YD158-YD170
2509B	24	M5	CQ		2-3	23-22-11	D02555B	B05			D04287J	B19			YC056-YD157
2509B	24	M5	CQ		2-5	23-22-11	D02555B	B05			D04289J	B02			YL951-YR328
2509R	24	M5	CQ		0-0	23-22-11	D02555B	A05			D04287J	A19			YC051-YD170
2509R	24	M5	CQ		0-0	23-22-11	D02555B	A05			D04289J	A02			YL951-YR328
2509ZI			CQ		0-0	23-22-11	D02555B	PERG	1A		D04287J	B20			YC051-YD170
2509ZI			CQ		0-0	23-22-11	D02555B	PERG	1A		D04289J	A07			YL951-YR328
2509ZO			CQ		0-0	23-22-11	D02555B	PERG	1A		D04287J	PERG	1F		YC051-YD170
2509ZO			CQ		0-0	23-22-11	D02555B	PERG	1A		D04289J	PERG	1F		YL951-YR328
2510B	24	M5	BC		3-0	34-49-11	D02501A	K14			D04287J	B03			YC051-YC055
2510B	24	M5	BC		2-9	34-49-11	D02501A	K14			D04287J	B03			YC056-YR328
2510R	24	M5	BC		0-0	34-49-11	D02501A	K15			D04287J	A03			ALL
2510ZI			BC		0-0	34-49-11	D02501A	PERG	1A		D04287J	B18			ALL
2510ZO			BC		0-0	34-49-11	D02501A	PERG	1A		D04287J	PERG	1F		ALL
2511B	24	M5	BD		3-0	34-55-11	D02501A	B12			D04287J	B04			YC051-YC055
2511B	24	M5	BD		2-9	34-55-11	D02501A	B12			D04287J	B04			YC056-YR328
2511R	24	M5	BD		0-0	34-55-11	D02501A	A13			D04287J	A04			ALL
2511ZI			BD		0-0	34-55-11	D02501A	PERG	1A		D04287J	B05			ALL
2511ZO			BD		0-0	34-55-11	D02501A	PERG	1A		D04287J	PERG	1F		ALL
2512B	24	M5	BE		2-11	34-55-21	D02501A	J10			D04285J	B03			YC051-YC055
2512B	24	M5	BE		2-8	34-55-21	D02501A	J10			D04285J	B03			YC056-YR328
2512R	24	M5	BE		0-0	34-55-21	D02501A	K10			D04285J	A03			ALL
2512ZI			BE		0-0	34-55-21	D02501A	PERG	1A		D04285J	B02			ALL
2512ZO			BE		0-0	34-55-21	D02501A	PERG	1A		D04285J	PERG	1F		ALL
2513B	24	M5	BN		3-0	34-57-11	D02501A	B11			D04287J	B06			YC051-YC055
2513B	24	M5	BN		2-9	34-57-11	D02501A	B11			D04287J	B06			YC056-YR328
2513R	24	M5	BN		0-0	34-57-11	D02501A	C11			D04287J	A06			ALL
2513ZI			BN		0-0	34-57-11	D02501A	PERG	1A		D04287J	A05			ALL
2513ZO			BN		0-0	34-57-11	D02501A	PERG	1A		D04287J	PERG	1F		ALL
2514B	24	M5	BO		2-11	34-57-21	D02501A	K07			D04285J	B04			YC051-YC055
2514B	24	M5	BO		2-8	34-57-21	D02501A	K07			D04285J	B04			YC056-YR328
2514R	24	M5	BO		0-0	23-51-51	D02501A	K08			D04285J	A04			YC051-YC052
2514R	24	M5	BO		0-0	34-57-21	D02501A	K08			D04285J	A04			YC053-YR328
2514ZI			BO		0-0	34-57-21	D02501A	PERG	1A		D04285J	B05			ALL
2514ZO			BO		0-0	34-57-21	D02501A	PERG	1A		D04285J	PERG	1F		ALL
2515B	24	Y2	BP		2-1	31-22-11	TB4101Y	A017	1A		D04371J	B06			YC051-YC055
2515B	24	Y2	BP		2-4	31-22-11	TB4101Y	A017	1A		D04371J	B06			YC056-YR328
2515R	24	Y2	BP		0-0	31-22-11	TB4101Y	B017	1A		D04371J	A06			ALL

WIRE LIST

D280A108

91-21-11

Section W0410

Page 43

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W0411	286A0411	E4-1 ELCTRONIC SHELF (continued)			
2515Z		BP	0-0 31-22-11 GB04101	ST.. 1A	ALL
2516B	24 M5 BS	2-5 23-22-11	D02555B	C02	YC051-YC055, YD158-YR328
2516B	24 M5 BS	2-3 23-22-11	D02555B	C02	YC056-YD157
2516R	24 M5 BS	0-0 23-22-11	D02555B	B02	ALL
2516ZI		BS	0-0 23-22-11	PERG 1A	ALL
2516ZO		BS	0-0 23-22-11	PERG 1A	ALL
2517B	24 M5 BT	2-4 23-22-11	D02555B	B03	YC051-YC055, YD158-YR328
2517B	24 M5 BT	2-1 23-22-11	D02555B	B03	YC056-YD157
2517R	24 M5 BT	0-0 23-22-11	D02555B	A03	ALL
2517ZI		BT	0-0 23-22-11	PERG 1A	ALL
2517ZO		BT	0-0 23-22-11	PERG 1A	ALL
2518B	24 M5 CB	2-11 23-12-11	D02501B	B03	YC051-YC055
2518B	24 M5 CB	2-8 23-12-11	D02501B	B03	YC056-YR328
2518R	24 M5 CB	0-0 23-12-11	D02501B	A03	ALL
2518ZI		CB	0-0 23-12-11	PERG 1A	ALL
2518ZO		CB	0-0 23-12-11	PERG 1A	ALL
2519B	24 M5 CC	3-0 23-12-11	D02501A	G06	YC051-YC055
2519B	24 M5 CC	2-9 23-12-11	D02501A	G06	YC056-YR328
2519R	24 M5 CC	0-0 23-12-11	D02501A	F06	ALL
2519ZI		CC	0-0 23-12-11	PERG 1A	ALL
2519ZO		CC	0-0 23-12-11	PERG 1A	ALL
2520B	24 M5 CD	2-9 23-12-21	D02501B	B04	YC051-YC055
2520B	24 M5 CD	2-7 23-12-21	D02501B	B04	YC056-YR328
2520R	24 M5 CD	0-0 23-12-21	D02501B	C04	ALL
2520ZI		CD	0-0 23-12-21	PERG 1A	ALL
2520ZO		CD	0-0 23-12-21	PERG 1A	ALL
2521B	24 M5 CE	2-11 23-12-21	D02501A	B09	YC051-YC055
2521B	24 M5 CE	2-8 23-12-21	D02501A	B09	YC056-YR328
2521R	24 M5 CE	0-0 23-12-21	D02501A	C09	ALL
2521ZI		CE	0-0 23-12-21	PERG 1A	ALL
2521ZO		CE	0-0 23-12-21	PERG 1A	ALL
2522B	24 M5 BV	2-2 23-22-11	D08123J	A16	YC051-YC055
2522B	24 M5 BV	2-0 23-22-11	D08123J	A16	YC056-YD157
2522B	24 M5 BV	2-3 23-22-11	D08123J	B14	YD158-YD170
2522B	24 M5 CR	2-3 23-22-11	D02555B	B06	YL951-YR328
2522R	24 M5 BV	0-0 23-22-11	D08123J	A15	YC051-YD157
2522R	24 M5 BV	0-0 23-22-11	D08123J	A14	YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0410

Page 44

Nov 12/2012



WIRE LIST
D280A108

91-21-11
Section W0410
Page 45
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W0411	286A0411	E4-1 ELCTRONIC SHELF (continued)			
2529ZO		CR	0-0 23-11-11 D08123J	PERG 1F D02501A	YC051-YD157
2529ZO		CX	0-0 23-12-31 D04289J	PERG 1F D02501B	YD158-YD170
2529ZO		DB	0-0 23-12-31 D02501B	PERG 1A D04289J	YL951-YR328
2530B	24	M5 DC	2-9 23-12-31 D02501A	G07 D04289J	YD158-YR328
2530R	24	M5 DC	0-0 23-12-31 D02501A	H07 D04289J	YD158-YR328
2530ZI		DC	0-0 23-12-31 D02501A	PERG 1A D04289J	YD158-YR328
2530ZO		DC	0-0 23-12-31 D02501A	PERG 1A D04289J	YD158-YR328
2532B	24	M5 BB	2-11 34-41-11 D02501A	CAP Y D04155J	YC051-YC052
2532B	24	M5 BB	2-11 34-41-11 D02501A	J08 D04155J	YC053-YC055
2532B	24	M5 BB	2-9 34-41-11 D02501A	J08 D04155J	YC056-YD170
2532B	24	M5 AQ	2-9 34-41-11 D02501A	J08 D04155J	YL951-YR328
2532R	24	M5 BB	0-0 34-41-11 D02501A	CAP Y D04155J	YC051-YC052
2532R	24	M5 BB	0-0 34-41-11 D02501A	D11 D04155J	YC053-YD170
2532R	24	M5 AQ	0-0 34-41-11 D02501A	D11 D04155J	YL951-YR328
2532ZI		BB	0-0 34-41-11 D02501A	DED D04155J	YC051-YD170
2532ZI		AQ	0-0 34-41-11 D02501A	DED D04155J	YL951-YR328
2532ZO		BB	0-0 34-41-11 D02501A	DED D04155J	YC051-YD170
2532ZO		AQ	0-0 34-41-11 D02501A	DED D04155J	YL951-YR328
2533B	24	M5 AS	3-3 23-29-11 D44145J	B01 TB4101Y	YC051-YC055
2533B	24	M5 AS	2-11 23-29-11 D44145J	B01 TB4101Y	YC056-YD157
2533R	24	M5 AS	0-0 23-29-11 D44145J	A01 TB4101Y	YC051-YD157
2533ZI		AS	0-0 23-29-11 D44145J	B02 TB4101Y	YC051-YD157
2533ZO		AS	0-0 23-29-11 D44145J	PERG 1F GB04101	YC051-YD157
2534B	24	M5 AT	2-4 23-29-11 TB4101Y	B077 1A D02501B	YC051-YD157
2534R	24	M5 AT	0-0 23-29-11 TB4101Y	A077 1A D02501B	YC051-YD157
2534ZI		AT	0-0 23-29-11 TB4101Y	B081 1A D02501B	YC051-YD157
2534ZO		AT	0-0 23-29-11 GB04101	ST.. 1A D02501B	YC051-YD157
2535B	24	M5 AU	2-6 23-29-11 D08123J	A14 TB4101Y	YC051-YC055
2535B	24	M5 AU	2-4 23-29-11 D08123J	A14 TB4101Y	YC056-YD157
2535R	24	M5 AU	0-0 23-29-11 D08123J	B14 TB4101Y	YC051-YD157
2535ZI		AU	0-0 23-29-11 D08123J	B15 TB4101Y	YC051-YD157
2535ZO		AU	0-0 23-29-11 D08123J	PERG 1F GB04101	YC051-YD157
2536B	24	M5 CS	2-8 23-12-31 D02501B	B05 D08123J	YC051-YC055
2536B	24	M5 CS	2-6 23-12-31 D02501B	B05 D08123J	YC056-YD157
2536R	24	M5 CS	0-0 23-12-31 D02501B	A05 D08123J	YC051-YD157
2536ZI		CS	0-0 23-12-31 D02501B	PERG 1A D08123J	YC051-YD157
2536ZO		CS	0-0 23-12-31 D02501B	PERG 1A D08123J	YC051-YD157
2537B	24	M5 CT	2-9 23-12-31 D02501A	G07 D08123J	YC051-YC055
2537B	24	M5 CT	2-7 23-12-31 D02501A	G07 D08123J	YC056-YD157

WIRE LIST

D280A108

91-21-11

Section W0410

Page 46

Nov 12/2012



WIRE LIST
D280A108

91-21-11
Section W0410
Page 47
Nov 12/2012

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411	286A0411			E4-1 ELCTRONIC SHELF (continued)											
2569B	24	M5	CY		2-8	23-11-21	D02501A	J06			D04285J	B19			YD158-YD170
2569B	24	M5	DE		2-8	23-11-21	D04285J	B19			D02501A	J06			YL951-YN260
2569R	24	M5	CY		0-0	23-11-21	D02501A	K06			D04285J	A19			YD158-YD170
2569R	24	M5	DE		0-0	23-11-21	D04285J	A19			D02501A	K06			YL951-YN260
2569ZI			CY		0-0	23-11-21	D02501A	PERG	1A		D04285J	A20			YD158-YD170
2569ZI			DE		0-0	23-11-21	D04285J	A20			D02501A	PERG	1A		YL951-YN260
2569ZO			CY		0-0	23-11-21	D02501A	PERG	1A		D04285J	PERG	1F		YD158-YD170
2569ZO			DE		0-0	23-11-21	D04285J	PERG	1F		D02501A	PERG	1A		YL951-YN260
2589B	24	M5	CW		2-7	23-11-11	D02501A	D10			D08123J	B13			YD158-YD170
2589R	24	M5	CW		0-0	23-11-11	D02501A	E10			D08123J	A13			YD158-YD170
2589ZI			CW		0-0	23-11-11	D02501A	PERG	1A		D08123J	B12			YD158-YD170
2589ZO			CW		0-0	23-11-11	D02501A	PERG	1A		D08123J	PERG	1F		YD158-YD170
2595B	24	Y2	BR		3-0	23-15-13	D02501A	B10			D41101J	A02			YC051-YD157
2595R	24	Y2	BR		0-0	23-15-13	D02501A	A10			D41101J	A01			YC051-YD157
2595Z			BR		0-0	23-15-13	D02501A	PERG	1A		D41101J	A03			YC051-YD157
2598B	24	Y2	BU		3-0	23-15-13	D02501A	G08			D41101J	A05			YC051-YD157
2598R	24	Y2	BU		0-0	23-15-13	D02501A	F08			D41101J	A04			YC051-YD157
2598Z			BU		0-0	23-15-13	D02501A	PERG	1A		D41101J	A06			YC051-YD157
2599B	24	Y2	DY		2-1	31-33-01	D04117J	B09			D10727B	K12			YD158-YD170
2599B	24	Y2	AV		2-1	31-33-01	D10727B	K12			D04117J	B09			YL951-YR328
2599R	24	Y2	DY		0-0	31-33-01	D04117J	A09			D10727B	J12			YD158-YD170
2599R	24	Y2	AV		0-0	31-33-01	D10727B	J12			D04117J	A09			YL951-YR328
2599Z			DY		0-0	31-33-01	D04117J	PERG	1F		D10727B	PERG	1A		YD158-YD170
2599Z			AV		0-0	31-33-01	D10727B	PERG	1A		D04117J	PERG	1F		YL951-YR328
2601B	24	Y2	EA		2-2	31-35-02	D04117J	B07			D10727A	G01			YD158-YD170
2601B	24	Y2	BB		2-2	31-35-02	D10727A	G01			D04117J	B07			YL951-YN260
2601B	24	Y2	BB		2-2	31-35-02	D10727A	G01	VP		D04117J	B07			YN501-YR328
2601R	24	Y2	EA		0-0	31-35-02	D04117J	A07			D10727A	F01			YD158-YD170
2601R	24	Y2	BB		0-0	31-35-02	D10727A	F01			D04117J	A07			YL951-YN260
2601R	24	Y2	BB		0-0	31-35-02	D10727A	F01	VP		D04117J	A07			YN501-YR328
2601Z			EA		0-0	31-35-02	D04117J	PERG	1F		D10727A	PERG	1A		YD158-YD170
2601Z			BB		0-0	31-35-02	D10727A	PERG	1A		D04117J	PERG	1F		YL951-YN260
2601Z			BB		0-0	31-35-02	D10727A	DED			D04117J	PERG	1F		YN501-YR328
2602B	24	Y2	DZ		2-1	31-35-02	D04117J	B08			D10727B	F11			YD158-YD170
2602B	24	Y2	BQ		2-1	31-35-02	D10727B	F11			D04117J	B08			YL951-YL954, YN231-YN260
2602B	24	Y2	EC		2-1	31-35-02	D10727B	F11			D04117J	B08			YL955-YL999, YN501
2602B	24	Y2	CT		2-1	31-35-02	D10727B	F11			D04117J	B08			YR301-YR328
2602R	24	Y2	DZ		0-0	31-35-02	D04117J	A08			D10727B	E11			YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0410

Page 48

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411	286A0411				E4-1 ELCTRONIC SHELF (continued)										
2602R	24	Y2	BQ		0-0	31-35-02	D10727B	E11			D04117J	A08			YL951-YL954, YN231-YN260
2602R	24	Y2	EC		0-0	31-35-02	D10727B	E11			D04117J	A08			YL955-YL999, YN501
2602R	24	Y2	CT		0-0	31-35-02	D10727B	E11			D04117J	A08			YR301-YR328
2602Z			DZ		0-0	31-35-02	D04117J	PERG	1F		D10727B	PERG	1A		YD158-YD170
2602Z			BQ		0-0	31-35-02	D10727B	PERG	1A		D04117J	PERG	1F		YL951-YL954, YN231-YN260
2602Z			EC		0-0	31-35-02	D10727B	PERG	1A		D04117J	PERG	1F		YL955-YL999, YN501
2602Z			CT		0-0	31-35-02	D10727B	PERG	1A		D04117J	PERG	1F		YR301-YR328
2603B	24	Y2	EE		2-3	23-27-32	D04115J	B07			D10727A	H10			YD158-YD170
2603B	24	Y2	CT		2-3	23-27-32	D04115J	B07			D10727A	H10	VP		YL951-YN260
2603R	24	Y2	EE		0-0	23-27-32	D04115J	A07			D10727A	G10			YD158-YD170
2603R	24	Y2	CT		0-0	23-27-32	D04115J	A07			D10727A	G10	VP		YL951-YN260
2603Z			EE		0-0	23-27-32	D04115J	PERG	1F		D10727A	PERG	1A		YD158-YD170
2603Z			CT		0-0	23-27-32	D04115J	PERG	1F		D10727A	DED			YL951-YN260
2604B	24	Y2	EF		2-3	23-27-32	D04115J	B08			D10727B	F15			YD158-YD170
2604B	24	Y2	EM		2-2	23-27-32	D04115J	B08			D10727B	F15			YL951-YR328
2604R	24	Y2	EF		0-0	23-27-32	D04115J	A08			D10727B	E15			YD158-YD170
2604R	24	Y2	EM		0-0	23-27-32	D04115J	A08			D10727B	E15			YL951-YR328
2604Z			EF		0-0	23-27-32	D04115J	PERG	1F		D10727B	PERG	1A		YD158-YD170
2604Z			EM		0-0	23-27-32	D04115J	PERG	1F		D10727B	PERG	1A		YL951-YR328
2607B	24	Y2	EG		2-1	23-27-33	D04009J	B09			D10727B	B11			YD158-YD170
2607B	24	Y2	EN		2-1	23-27-33	D04009J	B09			D10727B	B11	VP		YL951-YN260
2607R	24	Y2	EG		0-0	23-27-33	D04009J	A09			D10727B	A11			YD158-YD170
2607R	24	Y2	EN		0-0	23-27-33	D04009J	A09			D10727B	A11	VP		YL951-YN260
2607Z			EG		0-0	23-27-33	D04009J	PERG	1F		D10727B	PERG	1A		YD158-YD170
2607Z			EN		0-0	23-27-33	D04009J	PERG	1F		D10727B	DED			YL951-YN260
2608B	24	Y2	EH		2-1	23-27-33	D04009J	B10			D10727B	F12			YD158-YD170
2608B	24	Y2	CX		2-1	23-27-33	D04009J	B10			D10727B	F12			YL951-YR328
2608R	24	Y2	EH		0-0	23-27-33	D04009J	A10			D10727B	E12			YD158-YD170
2608R	24	Y2	CX		0-0	23-27-33	D04009J	A10			D10727B	E12			YL951-YR328
2608Z			EH		0-0	23-27-33	D04009J	PERG	1F		D10727B	PERG	1A		YD158-YD170
2608Z			CX		0-0	23-27-33	D04009J	PERG	1F		D10727B	PERG	1A		YL951-YR328
2610B	24	Y2	EL		2-3	23-27-37	D04007J	B03			D10727A	J13			YD158-YD170
2610B	24	Y2	DF		2-3	23-27-37	D04007J	B03			D10727A	J13			YL951-YR328
2610R	24	Y2	EL		0-0	23-27-37	D04007J	A03			D10727A	H13			YD158-YD170
2610R	24	Y2	DF		0-0	23-27-37	D04007J	A03			D10727A	H13			YL951-YR328
2610Z			EL		0-0	23-27-37	D04007J	PERG	1F		D10727A	PERG	1A		YD158-YD170
2610Z			DF		0-0	23-27-37	D04007J	PERG	1F		D10727A	PERG	1A		YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0410

Page 49

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411		286A0411			E4-1 ELCTRONIC SHELF (continued)											
2611B		24		Y2	EM	2-3	23-27-37	D04115J	B12			D10727A	B05			YD158-YD170
2611B		24		Y2	CZ	2-3	23-27-37	D04115J	B12			D10727A	B05			YL951-YR328
2611R		24		Y2	EM	0-0	23-27-37	D04115J	A12			D10727A	A05			YD158-YD170
2611R		24		Y2	CZ	0-0	23-27-37	D04115J	A12			D10727A	A05			YL951-YR328
2611Z					EM	0-0	23-27-37	D04115J	PERG	1F		D10727A	PERG	1A		YD158-YD170
2611Z					CZ	0-0	23-27-37	D04115J	PERG	1F		D10727A	PERG	1A		YL951-YR328
2612B		24		Y2	EN	2-3	23-27-37	D04115J	B13			D10727B	B12			YD158-YD170
2612B		24		Y2	DA	2-2	23-27-37	D04115J	B13			D10727B	B12			YL951-YR328
2612R		24		Y2	EN	0-0	23-27-37	D04115J	A13			D10727B	A12			YD158-YD170
2612R		24		Y2	DA	0-0	23-27-37	D04115J	A13			D10727B	A12			YL951-YR328
2612Z					EN	0-0	23-27-37	D04115J	PERG	1F		D10727B	PERG	1A		YD158-YD170
2612Z					DA	0-0	23-27-37	D04115J	PERG	1F		D10727B	PERG	1A		YL951-YR328
2613B		24		Y2	EP	2-2	23-27-37	D04007J	B08			D10727B	D07			YD158-YD170
2613B		24		Y2	DG	2-2	23-27-37	D04007J	B08			D10727B	D07			YL951-YR328
2613R		24		Y2	EP	0-0	23-27-37	D04007J	A08			D10727B	C07			YD158-YD170
2613R		24		Y2	DG	0-0	23-27-37	D04007J	A08			D10727B	C07			YL951-YR328
2613Z					EP	0-0	23-27-37	D04007J	PERG	1F		D10727B	PERG	1A		YD158-YD170
2613Z					DG	0-0	23-27-37	D04007J	PERG	1F		D10727B	PERG	1A		YL951-YR328
2614B		24		Y2	ER	2-3	23-27-37	D04007J	B09			D10727A	B10			YD158-YD170
2614B		24		Y2	DD	2-3	23-27-37	D04007J	B09			D10727A	B10			YL951-YR328
2614R		24		Y2	ER	0-0	23-27-37	D04007J	A09			D10727A	A10			YD158-YD170
2614R		24		Y2	DD	0-0	23-27-37	D04007J	A09			D10727A	A10			YL951-YR328
2614Z					ER	0-0	23-27-37	D04007J	PERG	1F		D10727A	PERG	1A		YD158-YD170
2614Z					DD	0-0	23-27-37	D04007J	PERG	1F		D10727A	PERG	1A		YL951-YR328
2617B		24		Y2	ES	2-1	23-27-38	D04117J	B11			D10727B	K10			YD158-YD170
2617B		24		Y2	DH	2-1	23-27-38	D04117J	B11			D10727B	K10			YL951-YL999, YN232-YR328
2617B		24		Y2	DH	2-1	23-27-38	D04117J	B11			D10727B	K10	VP		YN231
2617R		24		Y2	ES	0-0	23-27-38	D04117J	A11			D10727B	J10			YD158-YD170
2617R		24		Y2	DH	0-0	23-27-38	D04117J	A11			D10727B	J10			YL951-YL999, YN232-YR328
2617R		24		Y2	DH	0-0	23-27-38	D04117J	A11			D10727B	J10	VP		YN231
2617Z					ES	0-0	23-27-38	D04117J	PERG	1F		D10727B	PERG	1A		YD158-YD170
2617Z					DH	0-0	23-27-38	D04117J	PERG	1F		D10727B	PERG	1A		YL951-YL999, YN232-YR328
2617Z					DH	0-0	23-27-38	D04117J	PERG	1F		D10727B	DED			YN231
2618B		24		Y2	ET	2-3	23-27-39	D04115J	B15			D10727A	G06			YD158-YD170
2618B		24		Y2	KI	2-3	23-27-39	D10727A	G06			D04115J	B15			YL951-YR328
2618R		24		Y2	ET	0-0	23-27-39	D04115J	A15			D10727A	F06			YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0410

Page 50

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411	286A0411				E4-1 ELCTRONIC SHELF (continued)										
2618R	24		Y2	KI	0-0	23-27-39	D10727A	F06			D04115J	A15			YL951-YR328
2618Z				ET	0-0	23-27-39	D04115J	PERG	1F		D10727A	PERG	1A		YD158-YD170
2618Z				KI	0-0	23-27-39	D10727A	PERG	1A		D04115J	PERG	1F		YL951-YR328
2619B	24		Y2	DL	2-2	31-32-15	D04117J	B12			D10727A	E05			YD158-YD170
2619B	24		Y2	DJ	2-2	31-32-15	D04117J	B12			D10727A	E05			YL951-YR328
2619R	24		Y2	DL	0-0	31-32-15	D04117J	A12			D10727A	D05			YD158-YD170
2619R	24		Y2	DJ	0-0	31-32-15	D04117J	A12			D10727A	D05			YL951-YR328
2619Z				DL	0-0	31-32-15	D04117J	PERG	1F		D10727A	PERG	1A		YD158-YD170
2619Z				DJ	0-0	31-32-15	D04117J	PERG	1F		D10727A	PERG	1A		YL951-YR328
2620B	24		Y2	DP	2-1	34-61-23	D04009J	B02			D10727B	D12			YD158-YD170
2620B	24		Y2	DT	2-1	34-61-23	D04009J	B02			D10727B	D12			YL951-YR328
2620R	24		Y2	DP	0-0	34-61-23	D04009J	A02			D10727B	C12			YD158-YD170
2620R	24		Y2	DT	0-0	34-61-23	D04009J	A02			D10727B	C12			YL951-YR328
2620Z				DP	0-0	34-61-23	D04009J	PERG	1F		D10727B	PERG	1A		YD158-YD170
2620Z				DT	0-0	34-61-23	D04009J	PERG	1F		D10727B	PERG	1A		YL951-YR328
2621B	24		Y2	DR	2-1	34-61-23	D04117J	B13			D10727B	B14			YD158-YD170
2621B	24		Y2	DU	2-1	34-61-23	D04117J	B13			D10727B	B14			YL951-YR328
2621R	24		Y2	DR	0-0	34-61-23	D04117J	A13			D10727B	A14			YD158-YD170
2621R	24		Y2	DU	0-0	34-61-23	D04117J	A13			D10727B	A14			YL951-YR328
2621Z				DR	0-0	34-61-23	D04117J	PERG	1F		D10727B	PERG	1A		YD158-YD170
2621Z				DU	0-0	34-61-23	D04117J	PERG	1F		D10727B	PERG	1A		YL951-YR328
2622B	24		Y2	DS	2-1	34-61-25	D04009J	B03			D10727B	D11			YD158-YD170
2622B	24		Y2	DV	2-1	34-61-25	D04009J	B03			D10727B	D11	VP		YL951-YN260
2622R	24		Y2	DS	0-0	34-61-25	D04009J	A03			D10727B	C11			YD158-YD170
2622R	24		Y2	DV	0-0	34-61-25	D04009J	A03			D10727B	C11	VP		YL951-YN260
2622Z				DS	0-0	34-61-25	D04009J	PERG	1F		D10727B	PERG	1A		YD158-YD170
2622Z				DV	0-0	34-61-25	D04009J	PERG	1F		D10727B	DED			YL951-YN260
2623B	24		Y2	DT	2-1	34-61-25	D04009J	B04			D10727B	D04			YD158-YD170
2623B	24		Y2	DW	2-1	34-61-25	D04009J	B04			D10727B	D04	VP		YL951-YN260
2623R	24		Y2	DT	0-0	34-61-25	D04009J	A04			D10727B	C04			YD158-YD170
2623R	24		Y2	DW	0-0	34-61-25	D04009J	A04			D10727B	C04	VP		YL951-YN260
2623Z				DT	0-0	34-61-25	D04009J	PERG	1F		D10727B	PERG	1A		YD158-YD170
2623Z				DW	0-0	34-61-25	D04009J	PERG	1F		D10727B	DED			YL951-YN260
2624B	24		Y2	DU	2-1	34-61-25	D04009J	B05			D10727B	K06			YD158-YD170
2624B	24		Y2	DX	2-1	34-61-25	D04009J	B05			D10727B	K06	VP		YL951-YN260
2624R	24		Y2	DU	0-0	34-61-25	D04009J	A05			D10727B	J06			YD158-YD170
2624R	24		Y2	DX	0-0	34-61-25	D04009J	A05			D10727B	J06	VP		YL951-YN260
2624Z				DU	0-0	34-61-25	D04009J	PERG	1F		D10727B	PERG	1A		YD158-YD170
2624Z				DX	0-0	34-61-25	D04009J	PERG	1F		D10727B	DED			YL951-YN260

WIRE LIST

D280A108

91-21-11

Section W0410

Page 51

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411	286A0411			E4-1 ELCTRONIC SHELF (continued)											
2625B	24		Y2	DV	2-1	34-61-25	D04117J	B14			D10727B	REF	VP		YD158-YD170
2625B	24		Y2	EH	2-1	34-61-25	D04117J	B14			D10727B	REF	VP		YL951-YN260
2625R	24		Y2	DV	0-0	34-61-25	D04117J	A14			D10727B	REF	VP		YD158-YD170
2625R	24		Y2	EH	0-0	34-61-25	D04117J	A14			D10727B	REF	VP		YL951-YN260
2625Z				DV	0-0	34-61-25	D04117J	PERG	1F		D10727B	DED			YD158-YD170
2625Z				EH	0-0	34-61-25	D04117J	PERG	1F		D10727B	DED			YL951-YN260
2626B	24		Y2	DW	2-2	34-61-25	D04117J	B15			D10727A	F10			YD158-YD170
2626B	24		Y2	DR	2-2	34-61-25	D04117J	B15			D10727A	F10	VP		YL951-YN260
2626R	24		Y2	DW	0-0	34-61-25	D04117J	A15			D10727A	E10			YD158-YD170
2626R	24		Y2	DR	0-0	34-61-25	D04117J	A15			D10727A	E10	VP		YL951-YN260
2626Z				DW	0-0	34-61-25	D04117J	PERG	1F		D10727A	PERG	1A		YD158-YD170
2626Z				DR	0-0	34-61-25	D04117J	PERG	1F		D10727A	DED			YL951-YN260
2627B	24		Y2	DX	2-2	34-61-25	D04117J	B16			D10727A	H08			YD158-YD170
2627B	24		Y2	DP	2-2	34-61-25	D04117J	B16			D10727A	H08	VP		YL951-YN260
2627R	24		Y2	DX	0-0	34-61-25	D04117J	A16			D10727A	G08			YD158-YD170
2627R	24		Y2	DP	0-0	34-61-25	D04117J	A16			D10727A	G08	VP		YL951-YN260
2627Z				DX	0-0	34-61-25	D04117J	PERG	1F		D10727A	PERG	1A		YD158-YD170
2627Z				DP	0-0	34-61-25	D04117J	PERG	1F		D10727A	DED			YL951-YN260
2628B	24		Y2	EC	2-2	31-62-15	D04117J	B10			D10727A	REF	VP		YD158-YD170
2628B	24		Y2	BR	2-2	31-62-15	D04117J	B10			D10727A	D14	VP		YL951-YL954, YN231-YN260
2628B	24		Y2	ED	2-2	31-62-15	D04117J	B10			D10727A	D14	VP		YL955-YL999
2628R	24		Y2	EC	0-0	31-62-15	D04117J	A10			D10727A	REF	VP		YD158-YD170
2628R	24		Y2	BR	0-0	31-62-15	D04117J	A10			D10727A	C14	VP		YL951-YL954, YN231-YN260
2628R	24		Y2	ED	0-0	31-62-15	D04117J	A10			D10727A	C14	VP		YL955-YL999
2628Z				EC	0-0	31-62-15	D04117J	PERG	1F		D10727A	DED			YD158-YD170
2628Z				BR	0-0	31-62-15	D04117J	PERG	1F		D10727A	DED			YL951-YL954, YN231-YN260
2628Z				ED	0-0	31-62-15	D04117J	PERG	1F		D10727A	DED			YL955-YL999
2629B	24		Y2	ED	2-2	31-62-25	D04009J	B01			D10727A	REF	VP		YD158-YD170
2629B	24		Y2	BU	2-2	31-62-25	D04009J	B01			D10727A	B14	VP		YL951-YL954, YN231-YN260
2629B	24		Y2	EE	2-2	31-62-25	D04009J	B01			D10727A	B14	VP		YL955-YL999
2629R	24		Y2	ED	0-0	31-62-25	D04009J	A01			D10727A	REF	VP		YD158-YD170
2629R	24		Y2	BU	0-0	31-62-25	D04009J	A01			D10727A	A14	VP		YL951-YL954, YN231-YN260
2629R	24		Y2	EE	0-0	31-62-25	D04009J	A01			D10727A	A14	VP		YL955-YL999
2629Z				ED	0-0	31-62-25	D04009J	PERG	1F		D10727A	DED			YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0410

Page 52

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411	286A0411				E4-1 ELCTRONIC SHELF (continued)										
2629Z				BU	0-0	31-62-25	D04009J	PERG	1F		D10727A	DED			YL951-YL954, YN231-YN260
2629Z				EE	0-0	31-62-25	D04009J	PERG	1F		D10727A	DED			YL955-YL999
2631B	24	Y2	DM		2-1	34-61-21	D04009J	B06			D10727B	H13			YD158-YD170
2631B	24	Y2	KM		2-1	34-61-21	D04009J	B06			D10727B	H13			YL951-YR328
2631R	24	Y2	DM		0-0	34-61-21	D04009J	A06			D10727B	G13			YD158-YD170
2631R	24	Y2	KM		0-0	34-61-21	D04009J	A06			D10727B	G13			YL951-YR328
2631Z			DM		0-0	34-61-21	D04009J	PERG	1F		D10727B	PERG	1A		YD158-YD170
2631Z			KM		0-0	34-61-21	D04009J	PERG	1F		D10727B	PERG	1A		YL951-YR328
2632B	24	Y2	DN		2-1	34-61-21	D04117J	B17			D10727B	K15			YD158-YD170
2632B	24	Y2	KN		2-1	34-61-21	D04117J	B17			D10727B	K15			YL951-YR328
2632R	24	Y2	DN		0-0	34-61-21	D04117J	A17			D10727B	J15			YD158-YD170
2632R	24	Y2	KN		0-0	34-61-21	D04117J	A17			D10727B	J15			YL951-YR328
2632Z			DN		0-0	34-61-21	D04117J	PERG	1F		D10727B	PERG	1A		YD158-YD170
2632Z			KN		0-0	34-61-21	D04117J	PERG	1F		D10727B	PERG	1A		YL951-YR328
2633B	24	Y2	EI		2-3	23-27-33	D04115J	B03			D10727B	H12			YD158-YD170
2633B	24	Y2	EF		2-2	23-27-33	D04115J	B03			D10727B	H12			YL951-YN260
2633R	24	Y2	EI		0-0	23-27-33	D04115J	A03			D10727B	G12			YD158-YD170
2633R	24	Y2	EF		0-0	23-27-33	D04115J	A03			D10727B	G12			YL951-YN260
2633Z			EI		0-0	23-27-33	D04115J	PERG	1F		D10727B	PERG	1A		YD158-YD170
2633Z			EF		0-0	23-27-33	D04115J	PERG	1F		D10727B	PERG	1A		YL951-YN260
2634B	24	Y2	EJ		2-3	23-27-34	D04115J	B04			D10727B	H15			YD158-YD170
2634B	24	Y2	EJ		2-1	23-27-34	D02813B	38	VP		D10727B	H15			YL951-YN260
2634B	24	Y2	EJ		2-2	23-27-34	D04115J	B01			D10727B	H15			YN501-YR328
2634R	24	Y2	EJ		0-0	23-27-34	D04115J	A04			D10727B	G15			YD158-YD170
2634R	24	Y2	EJ		0-0	23-27-34	D02813B	37	VP		D10727B	G15			YL951-YN260
2634R	24	Y2	EJ		0-0	23-27-34	D04115J	A01			D10727B	G15			YN501-YR328
2634Z			EJ		0-0	23-27-34	D04115J	PERG	1F		D10727B	PERG	1A		YD158-YD170, YN501-YR328
2634Z			EJ		0-0	23-27-34	D02813B	DED			D10727B	PERG	1A		YL951-YN260
2635B	24	Y2	EV		2-2	23-27-36	D04009J	B08			D10727A	F02			YD158-YD170
2635R	24	Y2	EV		0-0	23-27-36	D04009J	A08			D10727A	E02			YD158-YD170
2635Z			EV		0-0	23-27-36	D04009J	PERG	1F		D10727A	PERG	1A		YD158-YD170
2636B	24	Y2	E1		2-3	23-27-36	D04115J	B18			D10727A	D10			YD158-YD170
2636R	24	Y2	E1		0-0	23-27-36	D04115J	A18			D10727A	C10			YD158-YD170
2636Z			E1		0-0	23-27-36	D04115J	PERG	1F		D10727A	PERG	1A		YD158-YD170
2637B	24	Y2	EW		2-3	23-27-36	D04115J	B19			D10727A	H07			YD158-YD170
2637R	24	Y2	EW		0-0	23-27-36	D04115J	A19			D10727A	G07			YD158-YD170
2637Z			EW		0-0	23-27-36	D04115J	PERG	1F		D10727A	PERG	1A		YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0410

Page 53

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411		286A0411					E4-1 ELCTRONIC SHELF (continued)									
2638B		24		Y2	EU	2-3	23-32-21	D04115J	B02			D10727B	D14			YD158-YD170
2638R		24		Y2	EU	0-0	23-32-21	D04115J	A02			D10727B	C14			YD158-YD170
2638Z					EU	0-0	23-32-21	D04115J	PERG	1F		D10727B	PERG	1A		YD158-YD170
2639B		24		Y2	AV	2-10	23-15-12	D02501B	E04			D41101J	A08			YC051-YC055
2639B		24		Y2	AV	2-11	23-15-12	D02501B	E04			D41101J	A08			YC056-YD157
2639R		24		Y2	AV	0-0	23-15-12	D02501B	D04			D41101J	A07			YC051-YD157
2639Z					AV	0-0	23-15-12	D02501B	PERG	1A		D41101J	A09			YC051-YD157
2641B		24		Y2	BQ	2-10	23-15-12	D02501B	E05			D41101J	B08			YC051-YC055
2641B		24		Y2	BQ	2-11	23-15-12	D02501B	E05			D41101J	B08			YC056-YD157
2641R		24		Y2	BQ	0-0	23-15-12	D02501B	E06			D41101J	B07			YC051-YD157
2641Z					BQ	0-0	23-15-12	D02501B	PERG	1A		D41101J	B10			YC051-YD157
2642B		22		X2	EO	1-9	34-61-15	D02813C	22			D40153J	B02			YL951-YN260
2642R		22		X2	EO	0-0	34-61-15	D02813C	21			D40153J	A02			YL951-YN260
2642Z					EO	0-0	34-61-15	GD02813	ST..	2		D40153J	PERG	1F		YL951-YN260
2644B		22		X2	LT	2-1	23-32-21	D10727B	D14			D02813B	44	VP		YL951-YN260
2644R		22		X2	LT	0-0	23-32-21	D10727B	C14			D02813B	43	VP		YL951-YN260
2644Z					LT	0-0	23-32-21	D10727B	PERG	1F		D02813B	DED			YL951-YN260
2646B		22		X2	KB	1-10	23-32-21	D02813B	19			D40151J	B03			YL951-YN260
2646R		22		X2	KB	0-0	23-32-21	D02813B	18			D40151J	A03			YL951-YN260
2646Z					KB	0-0	23-32-21	GD02813	ST..	2		D40151J	PERG	1F		YL951-YN260
2647B		22		X2	KC	1-10	23-32-21	D02813B	21			D40151J	B04			YL951-YN260
2647R		22		X2	KC	0-0	23-32-21	D02813B	20			D40151J	A04			YL951-YN260
2647Z					KC	0-0	23-32-21	GD02813	ST..	2		D40151J	PERG	1F		YL951-YN260
2650B		22		X2	EP	1-9	34-21-14	D02813C	2			D40153J	B04			YL951-YN260
2650R		22		X2	EP	0-0	34-21-14	D02813C	1			D40153J	A04			YL951-YN260
2650Z					EP	0-0	34-21-14	GD02813	ST..	2		D40153J	PERG	1F		YL951-YN260
2651B		22		X2	EQ	1-9	34-21-13	D02813B	35			D40153J	B05			YL951-YN260
2651R		22		X2	EQ	0-0	34-21-13	D02813B	34			D40153J	A05			YL951-YN260
2651Z					EQ	0-0	34-21-13	GD02813	ST..	2		D40153J	PERG	1F		YL951-YN260
2652B		22		X2	EB	2-4	46-11-51	D10727A	CAP	Y		D44139J	A08			YL951-YL954, YN231-YN235
2652R		22		X2	EB	0-0	46-11-51	D10727B	CAP	Y		D44139J	B08			YL951-YL954, YN231-YN235
2652Z					EB	0-0	46-11-51	D10727A	DED			D44139J	PERB			YL951-YL954, YN231-YN235
2653B		22		X2	EC	2-3	46-11-51	D10727B	CAP	Y		D44139J	A09			YL951-YL954, YN231-YN235
2653R		22		X2	EC	0-0	46-11-51	D10727B	CAP	Y		D44139J	B09			YL951-YL954, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W0410

Page 54

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411	286A0411				E4-1 ELCTRONIC SHELF (continued)										
2653Z				EC	0-0	46-11-51	D10727B	DED			D44139J	PERB			YL951-YL954, YN231-YN235
2654B	22	X2		ED	2-3	46-11-51	D10727B	CAP	Y		D44139J	A10			YL951-YL954, YN231-YN235
2654R	22	X2		ED	0-0	46-11-51	D10727B	CAP	Y		D44139J	B10			YL951-YL954, YN231-YN235
2654Z				ED	0-0	46-11-51	D10727B	DED			D44139J	PERB			YL951-YL954, YN231-YN235
2655B	22	X2		KE	1-2	23-32-21	SM00202		W		D40151J	B05			YL951-YN260
2655R	22	X2		KE	0-0	23-32-21	SM00201		W		D40151J	A05			YL951-YN260
2655Z				KE	0-0	23-32-21	SM00203		W		D40151J	PERG	1F		YL951-YN260
2656B	22	X2		KF	1-2	23-32-21	SM00202		W		D40151J	B10			YL951-YN260
2656R	22	X2		KF	0-0	23-32-21	SM00201		W		D40151J	A10			YL951-YN260
2656Z				KF	0-0	23-32-21	SM00203		W		D40151J	PERG	1F		YL951-YN260
2658B	24	Y2		ER	2-3	23-27-39	D10727A	REF	VP		D04115J	B05			YL951-YL954, YN231-YN235
2658R	24	Y2		ER	0-0	23-27-39	D10727A	REF	VP		D04115J	A05			YL951-YL954, YN231-YN235
2658Z				ER	0-0	23-27-39	D10727A	DED			D04115J	PERG	1F		YL951-YL954, YN231-YN235
2659B	24	Y2		EI	2-3	23-27-39	D10727A	REF	VP		D04115J	B04			YL951-YL954, YN231-YN235
2659R	24	Y2		EI	0-0	23-27-39	D10727A	REF	VP		D04115J	A04			YL951-YL954, YN231-YN235
2659Z				EI	0-0	23-27-39	D10727A	DED			D04115J	PERG	1F		YL951-YL954, YN231-YN235
2660B	24	Y2		DJ	2-1	34-45-21	D04117J	B18			D10727B	D08			YD158-YD170
2660B	24	Y2		DK	2-1	34-45-21	D04117J	B18			D10727B	D08			YL951-YR328
2660R	24	Y2		DJ	0-0	34-45-21	D04117J	A18			D10727B	C08			YD158-YD170
2660R	24	Y2		DK	0-0	34-45-21	D04117J	A18			D10727B	C08			YL951-YR328
2660Z				DJ	0-0	34-45-21	D04117J	PERG	1F		D10727B	DED			YD158-YD170
2660Z				DK	0-0	34-45-21	D04117J	PERG	1F		D10727B	PERG	1A		YL951-YR328
2661B	24	Y2		DK	2-1	34-45-21	D04009J	B07			D10727B	B10			YD158-YD170
2661B	24	Y2		DL	2-1	34-45-21	D04009J	B07			D10727B	B10			YL951-YR328
2661R	24	Y2		DK	0-0	34-45-21	D04009J	A07			D10727B	A10			YD158-YD170
2661R	24	Y2		DL	0-0	34-45-21	D04009J	A07			D10727B	A10			YL951-YR328
2661Z				DK	0-0	34-45-21	D04009J	PERG	1F		D10727B	DED			YD158-YD170
2661Z				DL	0-0	34-45-21	D04009J	PERG	1F		D10727B	PERG	1A		YL951-YR328
2690B	24	Y2		EG	2-1	31-35-02	D10727B	REF	VP		D04117J	B04			YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W0410

Page 55

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411		286A0411			E4-1 ELCTRONIC SHELF (continued)											
2690R		24		Y2	EG	0-0	31-35-02	D10727B	REF	VP		D04117J	A04			YN231-YN235
2690Z					EG	0-0	31-35-02	D10727B	DED			D04117J	PERG	1F		YN231-YN235
2695B		24		0T	MU	1-10	23-32-21	D02813B	58			D40151J	B01			YL951-YN260
2695W		24		0T	MU	0-0	23-32-21	D02813B	57			D40151J	A01			YL951-YN260
2695Z					MU	0-0	23-32-21	GD02813	ST..	2		D40151J	PERG	1F		YL951-YN260
2696B		24		7P	CW	1-10	23-32-21	D02813B	26			D40151J	A02			YL951-YN260
2696BN		24		7P	CW	0-0	23-32-21	D02813B	27			D40151J	B02			YL951-YN260
2696Z					CW	0-0	23-32-21	D02813B	39			D40151J	PERG	1F		YL951-YN260
2697B		22		X2	MW	1-4	23-32-21	D02813A	14			SM00202		W		YL951-YN260
2697R		22		X2	MW	0-0	23-32-21	D02813A	13			SM00201		W		YL951-YN260
2697Z					MW	0-0	23-32-21	GD02813	ST..	2		SM00203		W		YL951-YN260
2728B		24		Y2	GA	2-2	23-27-34	D04115J	B09			D10727B	K14			YN501-YR328
2728R		24		Y2	GA	0-0	23-27-34	D04115J	A09			D10727B	J14			YN501-YR328
2728Z					GA	0-0	23-27-34	D04115J	PERG	1F		D10727B	PERG	1A		YN501-YR328
2737B		24		Y2	FG	2-3	23-27-35	D10727B	D15	VP		D44139J	B03			YR318-YR328
2737R		24		Y2	FG	0-0	23-27-35	D10727B	C15	VP		D44139J	A03			YR318-YR328
2737Z					FG	0-0	23-27-35	D10727B	DED			D44139J	PERG	1F		YR318-YR328
3001B		24		Y3	AC	2-10	23-51-11	D02501B	G14			D04155J	A05			YC051-YC055
3001B		24		Y3	AC	2-7	23-51-11	D02501B	G14			D04155J	A05			YC056-YR328
3001R		24		Y3	AC	0-0	23-51-11	D02501B	H14			D04155J	B04			ALL
3001Y		24		Y3	AC	0-0	23-51-11	D02501B	F14			D04155J	B05			ALL
3001Z					AC	0-0	23-51-11	D02501B	DED			D04155J	PERG	1F		YC051-YD157
3001Z					AC	0-0	23-51-11	D02501B	PERG	1A		D04155J	B02			YD158-YR328
3002B		24		Y3	AD	2-10	23-51-11	D02501B	G15			D04155J	B08			YC051-YC055
3002B		24		Y3	AD	2-7	23-51-11	D02501B	G15			D04155J	B08			YC056-YR328
3002R		24		Y3	AD	0-0	23-51-11	D02501B	H15			D04155J	A08			ALL
3002Y		24		Y3	AD	0-0	23-51-11	D02501B	J04			D04155J	B09			ALL
3002Z					AD	0-0	23-51-11	D02501B	DED			D04155J	PERG	1F		YC051-YD157
3002Z					AD	0-0	23-51-11	D02501B	PERG	1A		D04155J	A12			YD158-YR328
3003B		24		Y3	AI	2-9	23-51-21	D02501B	C13			D04331J	A05			YC051-YC055
3003B		24		Y3	AI	2-6	23-51-21	D02501B	C13			D04331J	A05			YC056-YR328
3003R		24		Y3	AI	0-0	23-51-21	D02501B	D13			D04331J	B04			ALL
3003Y		24		Y3	AI	0-0	23-51-21	D02501B	F12			D04331J	B05			ALL
3003Z					AI	0-0	23-51-21	D02501B	DED			D04331J	PERG	1F		YC051-YD157
3003Z					AI	0-0	23-51-21	D02501B	PERG	1A		D04331J	B02			YD158-YR328
3004B		24		Y3	AJ	2-9	23-51-21	D02501B	A13			D04331J	B08			YC051-YC055
3004B		24		Y3	AJ	2-6	23-51-21	D02501B	A13			D04331J	B08			YC056-YR328
3004R		24		Y3	AJ	0-0	23-51-21	D02501B	A12			D04331J	A08			ALL
3004Y		24		Y3	AJ	0-0	23-51-21	D02501B	J06			D04331J	B09			ALL

WIRE LIST

D280A108

91-21-11

Section W0410

Page 56

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411	286A0411				E4-1 ELCTRONIC SHELF (continued)										
3004Z				AJ	0-0	23-51-21	D02501B	DED			D04331J	PERG	1F		YC051-YD157
3004Z				AJ	0-0	23-51-21	D02501B	PERG	1A		D04331J	B11			YD158-YR328
3005B	24	Y3	AO		2-7	23-51-31	D02501B	H11			D04153J	B08			YC051-YC055
3005B	24	Y3	AO		2-5	23-51-31	D02501B	H11			D04153J	B08			YC056-YR328
3005R	24	Y3	AO		0-0	23-51-31	D02501B	H10			D04153J	A08			ALL
3005Y	24	Y3	AO		0-0	23-51-31	D02501B	J08			D04153J	B09			ALL
3005Z				AO	0-0	23-51-31	D02501B	DED			D04153J	PERG	1F		YC051-YD157
3005Z				AO	0-0	23-51-31	D02501B	PERG	1A		D04153J	A09			YD158-YR328
3006B	24	Y3	BW		2-11	23-42-12	D02501B	G08			D04287J	B17			YC051-YC055
3006B	24	Y3	BW		2-8	23-42-12	D02501B	G08			D04287J	B17			YC056-YR328
3006R	24	Y3	BW		0-0	23-42-12	D02501B	G09			D04287J	A17			ALL
3006Y	24	Y3	BW		0-0	23-42-12	D02501B	F07			D04287J	A18			ALL
3006Z				BW	0-0	23-42-12	D02501B	PERG	1A		D04287J	A16			ALL
3026B	22	X3	CU		1-10	23-27-39	D10727A	E01			D11813	2			YL955-YL999, YN501-YR328
3026B	22	X3	FF		1-10	23-27-39	D10727A	E01			D11813	2			YN236-YN260
3026R	22	X3	CU		0-0	23-27-39	D10727A	H01			D11813	1			YL955-YL999, YN501-YR328
3026R	22	X3	FF		0-0	23-27-39	D10727A	H01			D11813	1			YN236-YN260
3026Y	22	X3	CU		0-0	23-27-39	D10727A	C01			D11813	3			YL955-YL999, YN501-YR328
3026Y	22	X3	FF		0-0	23-27-39	D10727A	C01			D11813	3			YN236-YN260
3026Z				CU	0-0	23-27-39	D10727A	PERG	1A		D11813			CU	YL955-YL999, YN501-YR328
3026Z				FF	0-0	23-27-39	D10727A	PERG	1A		D11813			CU	YN236-YN260
3501B	24	Y3	BY		3-1	23-41-11	D04161J	A02			TB4101Y	A001	1A		YC051-YC055
3501B	24	Y3	BY		3-3	23-41-11	D04161J	A02			TB4101Y	A001	1A		YC056-YR328
3501R	24	Y3	BY		0-0	23-41-11	D04161J	A01			TB4101Y	B001	1A		ALL
3501Y	24	Y3	BY		0-0	23-41-11	D04161J	B01			TB4101Y	A003	1A		ALL
3501Z				BY	0-0	23-41-11	D04161J			AA	GB04101	ST..	1A		ALL
3502B	24	Y3	BZ		3-1	23-41-11	D04161J	B03			TB4101Y	A001	1A		YC051-YC055
3502B	24	Y3	BZ		3-3	23-41-11	D04161J	B03			TB4101Y	A001	1A		YC056-YR328
3502R	24	Y3	BZ		0-0	23-41-11	D04161J	B02			TB4101Y	B001	1A		ALL
3502Y	24	Y3	BZ		0-0	23-41-11	D04161J	A03			TB4101Y	A003	1A		ALL
3502Z				BZ	0-0	23-41-11	D04161J			AA	GB04101	ST..	1A		ALL
3503B	24	Y3	CA		2-7	23-41-11	D02501B	G07			D04161J	A05			YC051-YC055
3503B	24	Y3	CA		2-4	23-41-11	D02501B	G07			D04161J	A05			YC056-YR328
3503R	24	Y3	CA		0-0	23-41-11	D02501B	G06			D04161J	A04			ALL
3503Y	24	Y3	CA		0-0	23-41-11	D02501B	F06			D04161J	B04			ALL

WIRE LIST

D280A108

91-21-11

Section W0410

Page 57

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0411	286A0411			E4-1 ELCTRONIC SHELF (continued)											
3503Z				CA	0-0	23-41-11	D02501B	PERG	1A		D04161J			AA	ALL
3507B	24	Y3		CF	2-5	23-51-31	D04153J	A18			D02501B	G10			YD158-YD170
3507B	24	Y3		AT	2-5	23-51-31	D04153J	A18			D02501B	G10			YL951-YN260, YR301-YR328
3507B	24	Y3		AU	2-5	23-51-31	D02501B	G10			D04153J	A18			YN501
3507R	24	Y3		CF	0-0	23-51-31	D04153J	B17			D02501B	F10			YD158-YD170
3507R	24	Y3		AT	0-0	23-51-31	D04153J	B17			D02501B	F10			YL951-YN260, YR301-YR328
3507R	24	Y3		AU	0-0	23-51-31	D02501B	F10			D04153J	B17			YN501
3507Y	24	Y3		CF	0-0	23-51-31	D04153J	A17			D02501B	H08			YD158-YD170
3507Y	24	Y3		AT	0-0	23-51-31	D04153J	A17			D02501B	H08			YL951-YN260, YR301-YR328
3507Y	24	Y3		AU	0-0	23-51-31	D02501B	H08			D04153J	A17			YN501
3507Z				CF	0-0	23-51-31	D04153J	B18			D02501B	PERG	1A		YD158-YD170
3507Z				AT	0-0	23-51-31	D04153J	B18			D02501B	PERG	1A		YL951-YN260, YR301-YR328
3507Z				AU	0-0	23-51-31	D02501B	PERG	1A		D04153J	B18			YN501
4259B	24	FS		EE	2-3	46-11-51	D10727B	CAP	Y		D44139J	A01			YL951-YL954, YN231-YN235
4259G	24	FS		EE	0-0	46-11-51	D10727B	CAP	Y		D44139J	A02			YL951-YL954, YN231-YN235
4259R	24	FS		EE	0-0	46-11-51	D10727B	CAP	Y		D44139J	B02			YL951-YL954, YN231-YN235
4259Y	24	FS		EE	0-0	46-11-51	D10727B	CAP	Y		D44139J	B01			YL951-YL954, YN231-YN235
4259Z				EE	0-0	46-11-51	D10727B	DED			D44139J	PERB			YL951-YL954, YN231-YN235
FRAA					0-0	23-41-11	D04161J	B05			D04161J			AA	ALL

WIRE LIST

D280A108

91-21-11

Section W0410

Page 58 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0420	286A0420				E4-2 SHELF (RIGHT WINDOW HEAT MODULES) RB2										
1001	20	X1	AA		1-11	30-41-12	D40068J	A03			TB5016	REF	=		ALL
1001Z			AA		0-0	30-41-12	D40068J	DED			TB5016	DED			ALL
1002	18	X1	AB		2-2	30-41-12	D40068J	F			TB5012	REF	=		YC051-YD170
1002	18	X1	AB		2-1	30-41-12	D40068J	F			TB5012	REF	=		YL951-YR328
1002Z			AB		0-0	30-41-12	D40068J	DED			TB5012	DED			ALL
2001B	20	X2	GA		1-9	30-41-12	D01046A	26			D40068J	A08			ALL
2001R	20	X2	GA		0-0	30-41-12	D01046A	13			D40068J	A07			ALL
2001Z			GA		0-0	30-41-12	GD04204	ST..	1A		D40068J	PERG	1F		YC051-YC057
2001Z			GA		0-0	30-41-12	GD04212	ST..	1F		D40068J	PERG	1F		YC058-YR328
2002B	24	Y2	GB		2-9	30-41-12	D01048A	12			TB4201Y	B021	1A		ALL
2002R	24	Y2	GB		0-0	30-41-12	D01048A	19			TB4201Y	A021	1A		ALL
2002Z			GB		0-0	30-41-12	GD04203	ST..	1A		GB04201	ST..	1A		YC051-YC057
2002Z			GB		0-0	30-41-12	GD04214	ST..	1F		GB04201	ST..	1A		YC058-YR328
2003B	20	X2	GC		2-1	30-41-12	D40068J	A06			D01048A	26			ALL
2003R	20	X2	GC		0-0	30-41-12	D40068J	A05			D01048A	13			ALL
2003Z			GC		0-0	30-41-12	D40068J	PERG	1F		GD04204	ST..	1A		YC051-YC057
2003Z			GC		0-0	30-41-12	D40068J	PERG	1F		GD04214	ST..	1F		YC058-YR328
2004B	24	Y2	GD		3-1	30-41-12	D01046A	12			TB4201Y	B021	1A		ALL
2004R	24	Y2	GD		0-0	30-41-12	D01046A	19			TB4201Y	A021	1A		ALL
2004Z			GD		0-0	30-41-12	GB04201	ST..	1A		GD04204	ST..	1A		YC051-YC057
2004Z			GD		0-0	30-41-12	GD04212	ST..	1F		GB04201	ST..	1A		YC058-YR328
2005B	24	Y2	GE		3-7	30-41-12	D41440J	B03			TB4201Y	B021	1A		YC051-YD170
2005B	24	Y2	GE		3-4	30-41-12	D41440J	B03			TB4201Y	B021	1A		YL951-YR328
2005R	24	Y2	GE		0-0	30-41-12	D41440J	A03			TB4201Y	A021	1A		ALL
2005Z			GE		0-0	30-41-12	D41440J	PERG	1F		GB04201	ST..	1A		ALL
5501	16	CQ			2-5	30-41-12	D42400J	2			D01046B	2			ALL
5502	16	PA			1-10	30-41-12	D01046B	7			GD04205	ST..	1		YC051-YC057
5502	16	PA			1-5	30-41-12	D01046B	7			GD04204	ST..	1		YC058-YR328
5503	16	PA			1-10	30-41-12	D01046B	5			GD04205	AC..	1		YC051-YC057
5503	16	PA			1-5	30-41-12	D01046B	5			GD04204	AC..	1		YC058-YR328
5504	20	PA			1-6	30-41-12	D01046A	6			GD04204	AC..	1A		YC051-YC057
5504	20	PA			2-0	30-41-12	D01046A	6			GD04203	AC..	1A		YC058-YR328
5505	24	PK			2-3	30-41-12	D01046A	5			D41440J	B04			YC051-YD170
5505	24	PK			2-0	30-41-12	D01046A	5			D41440J	B04			YL951-YR328
5506	20	PA			1-6	30-41-12	D01046A	10			GD04204	DC..	1A		YC051-YC057
5506	20	PA			2-0	30-41-12	D01046A	10			GD04203	DC..	1A		YC058-YR328
5507	24	PK			2-3	30-41-12	D01046A	24			D41440J	B05			YC051-YD170
5507	24	PK			2-0	30-41-12	D01046A	24			D41440J	B05			YL951-YR328
5508	24	PK			2-3	30-41-12	D01046A	25			D41440J	A04			YC051-YD170

WIRE LIST

D280A108

91-21-11

Section W0420

Page 1

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W0420	286A0420				E4-2 SHELF (RIGHT WINDOW HEAT MODULES) RB2 (continued)											
5508	24		PK		2-0	30-41-12		D01046A			25	D41440J		A04		YL951-YR328
5509	24		PK		2-3	30-41-12		D01046A			11	D41440J		A05		YC051-YD170
5509	24		PK		2-0	30-41-12		D01046A			11	D41440J		A05		YL951-YR328
5510	12		CQ		2-1	30-41-12		D42400J			1	D01048B		2		ALL
5511	12		HA		2-11	30-41-12		D01048B			7	GD04207	ST..	E		ALL
5512	12		HA		2-11	30-41-12		D01048B			5	GD04208	AC..	E		ALL
5513	20		PA		1-10	30-41-12		D01048A			6	GD04204	AC..	1A		YC051-YC057
5513	20		PA		1-8	30-41-12		D01048A			6	GD04203	AC..	1A		YC058-YR328
5514	24		PK		2-7	30-41-12		D41440J		A01		D01048A		5		YC051-YD170
5514	24		PK		2-4	30-41-12		D41440J		A01		D01048A		5		YL951-YR328
5515	20		PA		1-10	30-41-12		D01048A			10	GD04204	DC..	1A		YC051-YC057
5515	20		PA		1-8	30-41-12		D01048A			10	GD04203	DC..	1A		YC058-YR328
5516	24		PK		2-7	30-41-12		D41440J		B01		D01048A		24		YC051-YD170
5516	24		PK		2-4	30-41-12		D41440J		B01		D01048A		24		YL951-YR328
5517	24		PK		2-7	30-41-12		D41440J		A02		D01048A		25		YC051-YD170
5517	24		PK		2-4	30-41-12		D41440J		A02		D01048A		25		YL951-YR328
5518	24		PK		2-7	30-41-12		D41440J		B02		D01048A		11		YC051-YD170
5518	24		PK		2-4	30-41-12		D41440J		B02		D01048A		11		YL951-YR328
5519	20		PA		1-11	30-41-12		D01046A			1	TB5016		1	E	ALL
5520	20		PA		2-0	30-41-12		D01046A			7	TB5016		2	E	ALL
5521	20		PA		2-0	30-41-12		D01046A			8	TB5016		3	E	ALL
5522	20		PA		2-0	30-41-12		D01046A			14	TB5016		4	E	ALL
5523	20		PA		2-1	30-41-12		D01046A			20	TB5016		5	E	ALL
5524	20		PA		2-1	30-41-12		D01046A			21	TB5016		6	E	ALL
5525	18		PA		1-11	30-41-12		D01048A			7	TB5012		1	E	ALL
5526	18		PA		1-11	30-41-12		D01048A			8	TB5012		2	E	ALL
5527	18		PA		1-11	30-41-12		D01048A			14	TB5012		3	E	ALL
5528	18		PA		2-0	30-41-12		D01048A			20	TB5012		4	E	ALL
5529	18		PA		2-0	30-41-12		D01048A			21	TB5012		5	E	ALL
W0422	286A0422				E4-2 SHELF											
0001	24		PK		2-0	27-11-11		D40222J		A01		D40432J		A01		ALL
0002	24		PK		2-6	27-11-11		D40432J		A02		TB4201Y		A009	1A	YC051-YD153
0003	24		PK		2-6	27-11-11		D40432J		A03		TB4201Y		B009	1A	YC051-YD153
0004	24		PK		2-6	27-21-11		D40222J		A04		D40238J		A01		ALL
0005	24		PK		2-11	27-21-11		D40222J		A05		D40388J		B19		YC051-YD153
0006	24		PK		2-11	27-21-11		D40222J		A06		D40388J		B20		YC051-YD153
0008	20		PA		2-0	27-23-11		D40222J		A12		D43028J		B08		ALL
0009	20		PA		2-0	27-23-11		D40222J		A13		D43028J		A09		ALL

WIRE LIST

D280A108

91-21-11

Section W0420

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice Effectivity
W0422	286A0422	E4-2 SHELF (continued)		
0010	20 PA	2-8 27-23-11	D40222J A14	TB4201Y B001 1A ALL
0011	20 PA	3-8 27-23-11	D40484J B05	TB4201Y B005 1A YC051-YD170
0011	20 PA	3-9 27-23-11	D40484J B05	TB4201Y B005 1A YL951-YR328
0012	20 PA	3-9 27-23-11	D40484J B06	TB4201Y B001 1A ALL
0013	20 PA	2-4 27-23-11	D40238J B03	TB4201Y B005 1A ALL
0014	20 PA	3-5 27-23-11	D02586A 47	TB4201Y B005 1A YC051-YD170
0014	20 PA	3-6 27-23-11	D02586A 47	TB4201Y B005 1A YL951-YR328
0015	20 PA	3-6 27-23-11	D02586A 49	TB4201Y B001 1A ALL
0016	20 PA	2-0 27-23-11	D40222J B12	D43028J A02 ALL
0017	20 PA	2-0 27-23-11	D40222J B13	D43028J B02 ALL
0018	20 PA	2-3 27-41-12	D40222J B01	D40742J 1 ALL
0022	20 PA	2-3 27-41-12	D40222J B09	D40742J 2 ALL
0023	20 PA	2-3 27-41-12	D40222J B02	D40742J 3 ALL
0027	22 G5	2-0 27-54-11	D40222J B20	D43028J B05 ALL
0030	20 PA	3-0 27-61-11	D40540J A07	D43028J B07 ALL
0031	20 PA	3-0 27-61-11	D40540J B07	D43028J A08 ALL
0032	22 PA	1-8 27-62-11	GD04204 DC.. 1A	D02586A 38 YC051-YC057
0032	22 PA	2-10 27-62-11	GD04202 DC.. 1A	D02586A 38 YC058-YD170
0032	22 PA	2-11 27-62-11	GD04202 DC.. 1A	D02586A 38 YL951-YR328
0034	22 PA	1-8 27-62-11	GD04204 DC.. 1A	D02586B 9 YC051-YC057
0034	22 PA	2-10 27-62-11	GD04202 DC.. 1A	D02586B 9 YC058-YD170
0034	22 PA	2-11 27-62-11	GD04202 DC.. 1A	D02586B 9 YL951-YR328
0035	22 PA	1-8 27-62-11	GD04204 DC.. 1A	D02586B 26 YC051-YC057
0035	22 PA	2-10 27-62-11	GD04202 DC.. 1A	D02586B 26 YC058-YD170
0035	22 PA	2-11 27-62-11	GD04202 DC.. 1A	D02586B 26 YL951-YR328
0036	22 PA	2-2 27-62-11	D40474J A01	D02586B 47 YC051-YD170
0036	22 PA	1-11 27-62-11	D40474J A01	D02586B 47 YL951-YR328
0037	22 PA	2-2 27-62-11	D40474J A02	D02586B 33 YC051-YD170
0037	22 PA	1-11 27-62-11	D40474J A02	D02586B 33 YL951-YR328
0038	22 PA	2-2 27-62-11	D40474J A03	D02586B 39 YC051-YD170
0038	22 PA	1-11 27-62-11	D40474J A03	D02586B 39 YL951-YR328
0039	22 PA	2-2 27-62-11	D40474J A04	D02586B 31 YC051-YD170
0039	22 PA	1-11 27-62-11	D40474J A04	D02586B 31 YL951-YR328
0040	22 PA	3-3 27-62-11	D40388J A04	TB4201Y A013 1A YC051-YD170
0040	22 PA	3-4 27-62-11	D40388J A04	TB4201Y A013 1A YL951-YR328
0041	22 PA	2-3 27-62-11	D40388J A05	D02586A 40 YC051-YD170
0041	22 PA	2-4 27-62-11	D40388J A05	D02586A 40 YL951-YR328
0042	22 PA	2-0 27-62-11	D40484J A04	D02586B 20 ALL
0043	22 PA	2-0 27-62-11	D40484J A05	D02586B 28 ALL

WIRE LIST

D280A108

91-21-11

Section W0420

Page 3

Nov 12/2012

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0422	286A0422			E4-2 SHELF (continued)											
0044	22		PA		2-0	27-62-11	D40484J	A06			D02586B	52			ALL
0045	22		PA		2-0	27-62-11	D40484J	A07			D02586B	7			ALL
0046	22		PA		2-0	27-62-11	D40484J	B04			D02586A	19			ALL
0047	22		PA		2-2	27-62-11	D40474J	A07			D02586A	23			YC051-YD170
0047	22		PA		1-11	27-62-11	D40474J	A07			D02586A	23			YL951-YR328
0048	22		PA		2-2	27-62-11	D40474J	A06			D02586B	27			YC051-YD170
0048	22		PA		1-11	27-62-11	D40474J	A06			D02586B	27			YL951-YR328
0049	22		PA		2-11	27-62-11	D40222J	A09			D02586A	26			YC051-YD170
0049	22		PA		3-0	27-62-11	D40222J	A09			D02586A	26			YL951-YR328
0050	22		PA		2-2	27-62-11	D40474J	A05			D02586A	24			YC051-YD170
0050	22		PA		1-11	27-62-11	D40474J	A05			D02586A	24			YL951-YR328
0051	22		PA		2-7	29-11-11	D40222J	A17			D40370J	A05			ALL
0052	22		G5		2-4	29-11-11	D40356J	A01			D40140J	A01			YC051-YD170
0052	22		G5		2-5	29-11-11	D40356J	A01			D40140J	A01			YL951-YR328
0053	18		CQ		3-6	29-25-11	D40484J	F			D40238J	F			YC051-YD170
0053	18		CQ		3-7	29-25-11	D40484J	F			D40238J	F			YL951-YR328
0054	18		CQ		3-6	29-25-11	D40484J	G			D40238J	G			YC051-YD170
0054	18		CQ		3-7	29-25-11	D40484J	G			D40238J	G			YL951-YR328
0055	22		PA		2-11	29-23-11	D43028J	B10			D40472J	B03			YC051-YD170
0055	22		PA		3-0	29-23-11	D43028J	B10			D40472J	B03			YL951-YR328
0056	20		G5		3-1	29-23-11	D43028J	A10			D40484J	H			YC051-YD170
0056	20		G5		3-2	29-23-11	D43028J	A10			D40484J	H			YL951-YR328
0057	20		PA		2-11	31-31-15	D40388J	B01			D40222J	B04			ALL
0058	20		PA		2-11	31-31-15	D40388J	B02			D40222J	B03			ALL
0061	20		PA		2-2	33-33-11	D40382J	A16			D40388J	A18			ALL
0062	20		PA		3-5	33-36-11	D40382J	B14			D40584J	B06			ALL
0063	20		PA		3-5	33-36-11	D40382J	B15			D40584J	A06			ALL
0064	20		PA		3-5	33-36-12	D40382J	A14			D40584J	A07			ALL
0065	20		PA		3-5	33-36-12	D40382J	A15			D40584J	B07			ALL
0066	18		CQ		2-2	33-42-11	D40228J	F			D40164J	G			ALL
0067	20		PA		3-0	33-43-11	D40540J	A17			D40164J	B01			YC051-YD170
0067	20		PA		3-1	33-43-11	D40540J	A17			D40164J	B01			YL951-YR328
0068	20		G5		3-1	33-44-12	D40356J	B01			D40164J	A01			YC051-YD170
0068	20		G5		3-2	33-44-12	D40356J	B01			D40164J	A01			YL951-YR328
0069	16		PA		2-2	33-45-11	D40228J	K			D40164J	F			ALL
0070	22		PA		3-7	52-71-12	D40472J	B01			D40584J	B10			YC051-YD170
0070	22		PA		3-8	52-71-12	D40472J	B01			D40584J	B10			YL951-YR328
0071	22		PA		3-7	52-71-12	D40472J	B02			D40584J	A10			YC051-YD170
0071	22		PA		3-8	52-71-12	D40472J	B02			D40584J	A10			YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0420

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice Effectivity
W0422	286A0422	E4-2 SHELF (continued)		
0072	20 CQ	2-1 28-21-11	D40618J A02	D40140J A08 YC051-YD170
0072	20 CQ	2-2 28-21-11	D40618J A02	D40140J A08 YL951-YR328
0073	22 CQ	3-0 28-43-11	D40540J B14	D40164J A09 YC051-YD170
0073	22 CQ	3-1 28-43-11	D40540J B14	D40164J A09 YL951-YR328
0074	18 CQ	2-5 28-44-11	D40712J 20	D40164J H YC051-YD170
0074	18 CQ	2-4 28-44-11	D40712J 20	D40164J H YL951-YR328
0075	22 CQ	2-5 28-44-11	D40712J 11	D40164J B08 YC051-YD170
0075	22 CQ	2-4 28-44-11	D40712J 11	D40164J B08 YL951-YR328
0076	20 CQ	2-5 28-44-11	D40712J 19	D40164J B09 YC051-YD170
0076	20 CQ	2-4 28-44-11	D40712J 19	D40164J B09 YL951-YR328
0077	22 PA	3-1 30-11-11	D40356J A02	D40164J B02 YC051-YD170
0077	22 PA	3-2 30-11-11	D40356J A02	D40164J B02 YL951-YR328
0078	22 PA	3-1 30-11-11	D40356J B02	D40164J A02 YC051-YD170
0078	22 PA	3-2 30-11-11	D40356J B02	D40164J A02 YL951-YR328
0079	22 G5	2-8 27-54-11	D43028J B09	D42111J B03 ALL
0080	20 CQ	3-7 24-11-21	D40356J F	D10892B 5 ALL
0081	22 PA	3-7 24-11-21	D40540J A04	D10892A 61 ALL
0082	18 CQ	2-1 24-11-21	D40720J K	D40618J F ALL
0083	20 CQ	1-7 24-11-21	GD04201 DC.. 1A	D10892B 4 ALL
0084	20 PA	2-0 24-11-21	GD04202 ST.. 1A	D10892B 1 ALL
0085	22 G5	2-1 24-22-11	D40338J A07	D10898A 24 ALL
0086	22 PA	2-1 24-22-11	D40338J A05	D10898B 24 ALL
0087	22 G5	2-1 24-22-11	D40338J B05	D10898B 22 ALL
0088	22 PA	3-7 24-22-21	D40540J B04	D10892A 46 ALL
0089	22 PA	3-7 24-22-21	D40540J A05	D10892A 57 ALL
0090	22 PA	2-4 24-22-21	D40338J B04	D10892A 19 ALL
0091	22 PA	3-4 24-22-21	D40382J A05	D10892A 18 ALL
0092	22 PA	3-4 24-22-21	D40382J B05	D10892A 20 ALL
0093	22 PA	3-3 24-22-21	D40382J A04	D10892B 29 ALL
0094	22 PA	1-10 24-22-21	D10898B 35	D10892B 37 ALL
0095	22 PA	1-10 24-22-21	D10898B 37	D10892B 49 ALL
0096	22 PA	3-1 24-22-21	D10898A 35	D40382J B04 ALL
0097	22 PA	3-7 24-22-31	D40930J A01	D10898A 55 YC051-YD170
0097	22 PA	3-6 24-22-31	D40930J A01	D10898A 55 YL951-YR328
0098	22 PA	3-7 24-22-31	D40930J B04	D10898B 7 YC051-YD170
0098	22 PA	3-5 24-22-31	D40930J B04	D10898B 7 YL951-YR328
0099	22 PA	3-7 24-22-31	D40930J B01	D10898B 16 YC051-YD170
0099	22 PA	3-5 24-22-31	D40930J B01	D10898B 16 YL951-YR328
0100	22 PA	3-7 24-22-31	D40930J A02	D10898B 48 YC051-YD170

WIRE LIST

D280A108

91-21-11

Section W0420

Page 5

Nov 12/2012

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0422		286A0422				E4-2 SHELF (continued)									
	0100	22	PA		3-5	24-22-31	D40930J	A02			D10898B	48			YL951-YR328
	0101	22	PA		3-4	24-23-11	D40356J	A04			D10898B	23			ALL
	0102	22	PA		3-4	24-23-11	D40356J	B04			D10898A	30			YC051-YD170
	0102	22	PA		3-5	24-23-11	D40356J	B04			D10898A	30			YL951-YR328
	0103	22	G5		2-1	24-23-11	D40338J	B03			D10898A	21			ALL
	0104	22	G5		2-1	24-23-11	D40338J	A04			D10898A	19			ALL
	0105	22	PA		1-10	24-23-21	D10892B	7			D10898B	36			ALL
	0106	22	PA		3-1	24-23-21	D40382J	A03			D10898A	20			ALL
	0107	22	PA		3-1	24-23-21	D40382J	B03			D10898A	18			ALL
	0108	22	PA		1-11	24-23-21	D10892B	17			D10898A	56			ALL
	0109	22	PA		3-3	24-23-51	D40382J	A01			TB4201Y	A017	1A		ALL
	0110	22	PA		3-4	24-23-51	D40388J	A03			TB4201Y	A017	1A		ALL
	0111	22	PA		2-3	24-23-51	D40338J	A01			TB4201Y	A017	1A		ALL
	0112	22	PA		1-10	24-23-51	D10898B	44			TB4201Y	A017	1A		ALL
	0113	22	PA		3-2	24-23-51	D40388J	A02			D10898A	62			ALL
	0115	22	PA		2-1	24-28-41	D40338J	A02			D10898B	31			ALL
	0118	22	PA		3-0	24-28-41	D40382J	A02			D10898B	45			ALL
	0120	24	PK		1-10	24-28-41	D10892B	25			D10898B	63			ALL
	0121	24	PK		3-4	24-28-41	D40356J	A05			D10898B	61			ALL
	0122	24	PK		3-4	24-28-41	D40356J	B05			D10898B	50			ALL
	0123	24	PK		2-1	24-28-41	D40338J	A03			D10898B	27			ALL
	0124	18	PA		2-11	24-32-11	GD04205	AC..	1		D00104	6			YC051-YC057
	0124	18	PA		2-6	24-32-11	GD04204	AC..	1		D00104	6			YC058-YR328
	0125	08	CQ		3-0	24-32-11	GD01252	DC..	P		D00104	4			ALL
	0126	08	PA		3-11	24-32-11	TB5420	2	P		D00104	7			YC051-YD170
	0126	08	PA		4-0	24-32-11	TB5420	2	P		D00104	7			YL951-YR328
	0127	18	PA		2-5	24-32-11	D40370J	H			D00104	2			ALL
	0128	18	PA		2-5	24-32-11	D40370J	F			D00104	3			ALL
	0129	18	PA		2-5	24-32-11	D40370J	G			D00104	1			ALL
	0130	18	CQ		2-1	24-32-11	D40370J	J			D00106	3			ALL
	0131	18	CQ		2-1	24-32-11	D40370J	K			D00106	2			ALL
	0132	18	CQ		2-2	24-32-11	D40938J	F			D00106	1			ALL
	0133	08	CQ		3-4	24-32-11	TB5420	1	P		D00106	7			YC051-YD170
	0133	08	CQ		3-5	24-32-11	TB5420	1	P		D00106	7			YL951-YR328
	0134	08	CQ		2-9	24-32-11	GD01220	DC..	P		D00106	4			ALL
	0135	18	PA		2-7	24-32-11	GD04205	AC..	1		D00106	6			YC051-YC057
	0135	18	PA		2-2	24-32-11	GD04204	AC..	1		D00106	6			YC058-YR328
	0136	22	PA		3-7	24-41-11	D40930J	A05			D10898B	20			YC051-YD170
	0136	22	PA		3-5	24-41-11	D40930J	A05			D10898B	20			YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0420

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice Effectivity
W0422	286A0422	E4-2 SHELF (continued)		
0137	20 CQ	3-4 24-41-11	D40356J G	D10898B 5 ALL
0139	22 PA	1-0 24-41-11	SM00003 W	D10898A 49 ALL
0140	22 PA	1-0 24-41-11	SM00004 W	D10898A 61 ALL
0141	22 PA	1-0 24-41-11	SM00005 W	D10898A 8 ALL
0142	20 PA	1-9 24-41-11	GD04202 DC.. 1A	D10898B 4 ALL
0143	20 PA	2-1 24-41-11	D40338J J	D10898B 3 ALL
0144	20 PA	1-9 24-41-11	GD04201 ST.. 1A	D10898B 1 ALL
0145	22 G5	2-8 24-22-11	D40382J B18	D40930J B05 YC051-YD170
0145	22 G5	2-6 24-22-11	D40382J B18	D40930J B05 YL951-YR328
0146	22 G5	2-8 24-22-31	D40382J A18	D40930J A06 YC051-YD170
0146	22 G5	2-6 24-22-31	D40382J A18	D40930J A06 YL951-YR328
0147	24 PK	3-5 31-62-24	D40388J A19	D10892A 33 ALL
0148	22 PA	2-5 21-27-31	D40484J A08	D40382J B20 YC051-YD170
0148	22 PA	2-6 21-27-31	D40484J A08	D40382J B20 YL951-YR328
0149	20 G5	3-7 22-11-12	D42111J A01	D02586B 56 ALL
0150	20 G5	3-7 22-11-12	D42111J A02	D02586B 55 ALL
0151	20 PA	3-5 33-36-11	D40618J B04	D40584J A04 YC051-YD170
0151	20 PA	3-6 33-36-11	D40618J B04	D40584J A04 YL951-YR328
0152	20 PA	3-5 33-36-12	D40618J B05	D40584J B04 YC051-YD170
0152	20 PA	3-6 33-36-12	D40618J B05	D40584J B04 YL951-YR328
0153	20 CQ	2-11 28-44-11	D40164J B05	D40618J B07 YL951-YR328
0154	20 G5	3-4 22-11-11	D40484J B03	D10898B 52 YC051-YD170
0154	20 G5	3-5 22-11-11	D40484J B03	D10898B 52 YL951-YR328
0155	20 G5	2-0 22-11-12	D40484J B01	D02586A 55 ALL
0156	20 G5	2-0 22-11-12	D40484J B02	D02586A 53 ALL
0157	20 G5	2-1 22-11-11	D42111J B01	D10898B 65 ALL
0158	22 PA	2-8 21-25-11	D40388J B12	D40474J A08 YC051-YD170
0158	22 PA	2-6 21-25-11	D40388J B12	D40474J A08 YL951-YR328
0160	24 PK	2-6 21-31-24	D40484J B08	D40388J B14 YC051-YD157
0162	20 PA	3-0 27-61-11	D43028J B06	D40540J A03 ALL
0163	20 PA	3-0 27-61-11	D43028J A07	D40540J B03 ALL
0164	24 PK	2-8 27-11-11	D40222J A02	TB4201Y A009 1A YC051-YD153
0165	24 PK	2-8 27-11-11	D40222J A03	TB4201Y B009 1A YC051-YD153
0166	24 PK	3-5 27-11-11	D40388J B16	TB4201Y B009 1A YC051-YD153
0167	24 PK	3-5 27-11-11	D40388J B17	TB4201Y A009 1A YC051-YD153
0168	22 PA	2-7 27-62-11	D40388J B13	D40484J A03 YL953-YL999, YR301-YR328
0169	22 PA	2-7 27-62-11	D40388J B10	D40484J B10 YL953-YL999, YR301-YR328

WIRE LIST
D280A108

91-21-11
Section W0420
Page 7
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0422	286A0422			E4-2 SHELF (continued)											
0170	22		PA		2-4	29-23-11	D40472J	B04			D40388J	B05			YC051-YD170
0170	22		PA		2-5	29-23-11	D40472J	B04			D40388J	B05			YL951-YR328
0171	20		PA		2-2	28-23-11	D40938J	B06			D40540J	B11			YC051-YD170
0171	20		PA		2-3	28-23-11	D40938J	B06			D40540J	B11			YL951-YR328
0172	20		PA		2-2	28-23-11	D40938J	B07			D40540J	B12			YC051-YD157
0173	20		PA		2-2	28-23-11	D40938J	B08			D40540J	B13			YC051-YD170
0173	20		PA		2-3	28-23-11	D40938J	B08			D40540J	B13			YL951-YR328
0174	20		CQ		3-4	28-22-11	D40540J	A12			D40714J	A06			YC051-YD170
0174	20		CQ		3-5	28-22-11	D40540J	A12			D40714J	A06			YL951-YR328
0175	20		CQ		3-4	28-22-11	D40540J	A13			D40714J	A07			YC051-YD170
0175	20		CQ		3-5	28-22-11	D40540J	A13			D40714J	A07			YL951-YR328
0176	20		CQ		3-4	28-22-11	D40540J	A14			D40714J	A08			YC051-YD170
0176	20		CQ		3-5	28-22-11	D40540J	A14			D40714J	A08			YL951-YR328
0177	20		CQ		2-4	28-43-11	TB4201Y	A029	1A		D40714J	A01			YC051-YD157
0178	20		CQ		3-4	28-43-11	D40540J	B15			D40714J	B01			YC051-YD157
0178	22		CQ		3-4	28-43-11	D40540J	B15			D40714J	B01			YD158-YD170
0178	22		CQ		3-5	28-43-11	D40540J	B15			D40714J	B01			YL951-YR328
0179	22		G5		3-4	27-62-11	TB4201Y	A013	1A		D02586A	42			ALL
0180	22		G5		3-7	27-62-11	TB4201Y	A013	1A		D40484J	A10			ALL
0181	24		PK		2-10	31-62-24	D40388J	A20			TB4201Y	A029	1A		YC051-YD157
0182	22		CQ		3-0	28-43-11	D40540J	A15			TB4201Y	A029	1A		YC051-YD157
0184	22		PA		3-7	24-22-31	D10898A	29			D40930J	B06			YC051-YD170
0184	22		PA		3-6	24-22-31	D10898A	29			D40930J	B06			YL951-YR328
0214	24		PK		2-3	21-31-23	D40712J	7			D40618J	A06			YC067-YD157
0215	24		PK		2-3	21-31-23	D40712J	8			D40618J	A07			YC067-YD157
0216	20		PA		2-3	21-31-23	D40712J	9			D40618J	A08			YC067-YD157
0220	22		GA		3-0	24-28-41	D40338J	B01			D10898B	32			YC051-YC057
0220	22		GA		2-1	24-28-41	D40338J	B01			D10898B	32			YC058-YD153
0220	22		PA		2-1	24-28-41	D40338J	B01			D10898B	32			YD154-YR328
0221	22		GA		4-0	24-28-41	D40382J	B02			D10898B	43			YC051-YC057
0221	22		GA		3-0	24-28-41	D40382J	B02			D10898B	43			YC058-YD153
0221	22		PA		3-0	24-28-41	D40382J	B02			D10898B	43			YD154-YR328
0222	24		GK		5-0	24-28-41	D40930J	A07			D10898B	56			YC051-YC057
0222	24		GK		3-7	24-28-41	D40930J	A07			D10898B	56			YC058-YD153
0222	24		PK		3-7	24-28-41	D40930J	A07			D10898B	56			YD154-YD170
0222	24		PK		3-5	24-28-41	D40930J	A07			D10898B	56			YL951-YR328
0223	24		GK		5-0	24-28-41	D40930J	B07			D10898B	57			YC051-YC057
0223	24		GK		3-7	24-28-41	D40930J	B07			D10898B	57			YC058-YD153
0223	24		PK		3-7	24-28-41	D40930J	B07			D10898B	57			YD154-YD170

WIRE LIST

D280A108

91-21-11

Section W0420

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0422	286A0422				E4-2 SHELF (continued)											
0223	24		PK		3-5	24-28-41		D40930J		B07		D10898B		57		YL951-YR328
0224	24		PK		2-0	27-11-11		D40222J		A02		D40432J		A02		YD154-YR328
0225	24		PK		2-0	27-11-11		D40222J		A03		D40432J		A03		YD154-YR328
0226	24		PK		2-11	27-11-11		D40222J		A15		D40388J		B17		YD154-YR328
0227	24		PK		2-11	27-11-11		D40222J		B15		D40388J		B16		YD154-YR328
0228	24		PK		2-6	27-21-11		D40222J		A05		D40238J		A07		YD154-YR328
0229	24		PK		2-6	27-21-11		D40222J		A06		D40238J		B07		YD154-YR328
0230	24		PK		2-11	27-21-11		D40222J		A16		D40388J		B19		YD154-YR328
0231	24		PK		2-11	27-21-11		D40222J		B16		D40388J		B20		YD154-YR328
0232	24		PK		3-10	21-31-24		D40484J		B08		D42111J		A10		YD158-YR328
0233	24		PK		1-9	21-31-23		D40472J		B08		D40618J		A06		YD158-YR328
0234	24		PK		1-9	21-31-23		D40472J		B09		D40618J		A07		YD158-YR328
0235	20		PA		1-9	21-31-23		D40472J		B10		D40618J		A08		YD158-YR328
0236	20		PA		2-9	21-31-23		D40714J		B06		D40712J		2		YD158-YD170
0236	20		PA		2-8	21-31-23		D40714J		B06		D40712J		2		YL951-YR328
0237	24		PK		2-9	21-31-23		D40714J		B07		D40712J		10		YD158-YD170
0237	24		PK		2-8	21-31-23		D40714J		B07		D40712J		10		YL951-YR328
0238	20		PA		2-4	28-23-11		D40938J		B07		D40169J		B09		YD158-YD170
0238	20		PA		2-1	28-23-11		D40938J		B07		D40169J		B09		YL951-YR328
0239	20		PA		2-2	28-23-11		D40540J		B12		D40169J		A10		YD158-YD170
0239	20		PA		1-10	28-23-11		D40540J		B12		D40169J		A10		YL951-YR328
0240	22		CQ		2-5	28-43-11		D40540J		B17		D40388J		A20		YD158-YD170
0240	22		CQ		2-6	28-43-11		D40540J		B17		D40388J		A20		YL951-YR328
0241	22		CQ		2-2	28-43-11		D40714J		A01		TB4201Y		B019	1A	YD158-YR328
0242	22		CQ		3-6	28-43-11		D40540J		A15		TB4201Y		B019	1A	YD158-YR328
0243	22		CQ		3-7	28-43-11		D40169J		A09		TB4201Y		A019	1A	YD158-YD170
0243	22		CQ		3-4	28-43-11		D40169J		A09		TB4201Y		A019	1A	YL951-YR328
0247	20		PA		2-2	28-23-11		D40938J		A06		D40472J		B07		YL951-YR328
0249	20		PA		2-2	28-23-11		D40938J		A07		D40472J		F		YL951-YR328
0250	20		PA		1-10	28-23-11		D40540J		A01		D40169J		B10		YL951-YR328
0291	22		PA		2-2	23-42-11		D40540J		A02		D40484J		B07		YL951-YR328
0292	22		PA		2-2	23-42-11		D40540J		A18		D40484J		B10		YL951-YL952, YN231-YN501
0292	22		PA		1-10	23-42-11		D40540J		A18		D40618J		B10		YL953-YL999, YR301-YR328
0293	22		PA		2-2	23-42-11		D40540J		A16		D40484J		A03		YL951-YL952, YN231-YN501
0293	22		PA		1-10	23-42-11		D40540J		A16		D40618J		B09		YL953-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W0420

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice Effectivity
W0422	286A0422	E4-2 SHELF (continued)		
0300	22 PA	2-9 31-31-15	D40618J B02	D43028J A06 YC065-YD170
0300	22 PA	2-10 31-31-15	D40618J B02	D43028J A06 YL951-YR328
0501	20 PA	1-9 24-28-41	D10898B 10	GD04201 ST.. 1A ALL
0502	20 G5	3-11 27-81-51	D40930J A03	TB4201Y A001 1A YC051-YD170
0502	20 G5	3-9 27-81-51	D40930J A03	TB4201Y A001 1A YL951-YR328
0503	20 G5	2-4 27-81-51	TB4201Y A001 1A	D40238J A02 ALL
0504	20 G5	2-9 27-81-51	D40228J A01	TB4201Y A001 1A ALL
0505	20 G5	2-6 27-81-51	D40228J B01	D40238J B01 ALL
0506	20 G5	2-5 27-81-51	D42111J B04	D40238J A03 ALL
0507	20 G5	2-5 27-81-51	D42111J B05	D40238J B02 ALL
1001	20 X1 AA	2-11 27-62-11	D40222J A08	D02586A 8 ALL
1001Z		0-0 27-62-11	D40222J A07	GD04204 ST.. 1A YC051-YC057
1001Z		0-0 27-62-11	D40222J A07	GD04216 ST.. 1F YC058-YR328
1003	20 X1 AC	2-11 27-62-11	D40222J B08	D02586B 5 ALL
1003Z		0-0 27-62-11	D40222J B07	GD04204 ST.. 1A YC051-YC057
1003Z		0-0 27-62-11	D40222J B07	GD04216 ST.. 1F YC058-YR328
1004	20 HE AD	2-8 73-22-11	D40474J B01	D40388J B11 YC051-YD170
1004	20 HE AD	2-6 73-22-11	D40474J B01	D40388J B11 YL951-YR328
1004Z		0-0 73-22-11	D40474J PERG 1F	D40388J PERG 1F ALL
1101	20 X1 BN	3-4 27-62-11	D40388J A10	D40222J A10 ALL
1101Z		0-0 27-62-11	D40388J A17	D40222J B10 ALL
1102	20 X1 BP	2-1 27-62-11	D02586B 12	D40484J A09 ALL
1102Z		0-0 27-62-11	GD04204 ST.. 1A	D40484J B09 YC051-YC057
1102Z		0-0 27-62-11	GD04216 ST.. 1F	D40484J B09 YC058-YR328
1103	20 X1 BO	2-11 27-62-11	D40222J B05	D02586A 3 ALL
1103Z		0-0 27-62-11	D40222J B06	GD04204 ST.. 1A YC051-YC057
1103Z		0-0 27-62-11	D40222J B06	GD04216 ST.. 1F YC058-YR328
2001B	24 Y2 GA	2-6 73-21-11	D40484J A01	D40388J B09 YC051-YD170
2001B	24 Y2 GA	2-7 73-21-11	D40484J A01	D40388J B09 YL951-YR328
2001R	24 Y2 GA	0-0 73-21-11	D40484J A02	D40388J B08 ALL
2001Z		0-0 73-21-11	D40484J PERG 1F	D40388J PERG 1F ALL
2002B	20 X2 GB	3-2 24-21-21	D40720J F	D10892B 56 ALL
2002R	20 X2 GB	0-0 24-21-21	D40720J G	D10892B 55 ALL
2002Z		0-0 24-21-21	D40720J A10	GD04209 ST.. 1A ALL
2003B	22 PB GC	3-10 24-22-21	D40474J A09	D10892A 55 YC051-YD170
2003B	22 PB GC	3-8 24-22-21	D40474J A09	D10892A 55 YL951-YR328
2003R	22 PB GC	0-0 24-22-21	D40474J A10	D10892A 43 ALL
2004B	22 PB GD	3-2 24-11-21	D40720J A02	D10892B 15 ALL
2004R	22 PB GD	0-0 24-11-21	D40720J B02	D10892B 27 ALL

WIRE LIST

D280A108

91-21-11

Section W0420

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0422	286A0422			E4-2 SHELF (continued)											
2005B	22	X2	GE		3-7	24-23-11	D40930J	B03			D10898B	29			YC051-YD170
2005B	22	X2	GE		3-5	24-23-11	D40930J	B03			D10898B	29			YL951-YR328
2005R	22	X2	GE		0-0	24-23-11	D40930J	A04			D10898B	42			ALL
2005Z			GE		0-0	24-23-11	D40930J	DED			D10898B	DED			ALL
2006B	22	X2	GF		3-2	24-23-21	D40938J	B02			D10892A	10			ALL
2006R	22	X2	GF		0-0	24-23-21	D40938J	A02			D10892A	1			ALL
2006Z			GF		0-0	24-23-21	D40938J	DED			D10892A	DED			ALL
2007B	22	PB	GG		3-1	24-23-51	D40388J	A06			D10898B	53			ALL
2007R	22	PB	GG		0-0	24-23-51	D40388J	A07			D10898B	66			ALL
2008B	22	PB	GH		3-6	24-28-11	D40540J	B20			D10892B	60			YC051-YD170
2008B	22	PB	GH		3-7	24-28-11	D40540J	B20			D10892B	60			YL951-YR328
2008R	22	PB	GH		0-0	24-28-11	D40540J	A20			D10892B	47			ALL
2009B	22	PB	GI		3-3	24-28-41	D40540J	B08			D10898B	28			YC051-YD170
2009B	22	PB	GI		3-4	24-28-41	D40540J	B08			D10898B	28			YL951-YR328
2009R	22	PB	GI		0-0	24-28-41	D40540J	A08			D10898B	41			ALL
2010B	22	PB	GJ		2-1	24-28-41	D42111J	A04			D10898A	57			ALL
2010R	22	PB	GJ		0-0	24-28-41	D42111J	A03			D10898A	44			ALL
2011B	24	Y2	GK		2-8	24-33-11	D40618J	A01			D00104	8			YC051-YD170
2011B	24	Y2	GK		2-9	24-33-11	D40618J	A01			D00104	8			YL951-YR328
2011R	24	Y2	GK		0-0	24-33-11	D40618J	B01			D00104	5			ALL
2011Z			GK		0-0	24-33-11	D40618J	DED			D00104	DED			ALL
2012B	24	Y2	GL		2-4	24-33-11	D40618J	A03			D00106	8			YC051-YD170
2012B	24	Y2	GL		2-5	24-33-11	D40618J	A03			D00106	8			YL951-YR328
2012R	24	Y2	GL		0-0	24-33-11	D40618J	B03			D00106	5			ALL
2012Z			GL		0-0	24-33-11	D40618J	DED			D00106	DED			ALL
2013B	22	PB	GM		2-8	24-41-11	D40388J	A11			SM00002	9			YC051-YC055
2013R	22	PB	GM		0-0	24-41-11	D40388J	A12			SM00001	9			YC051-YC055
2014B	22	PB	GN		0-11	24-41-11	SM00002		9		D10898B	67			YC051-YC055
2014B	22	PB	GN		3-1	24-41-11	D40388J	A11			D10898B	67			YC056-YR328
2014R	22	PB	GN		0-0	24-41-11	SM00001		9		D10898B	54			YC051-YC055
2014R	22	PB	GN		0-0	24-41-11	D40388J	A12			D10898B	54			YC056-YR328
2015B	22	PB	GP		2-8	24-41-11	D40388J	A13			SM00003		W		ALL
2015R	22	PB	GP		0-0	24-41-11	D40388J	A14			SM00004		W		ALL
2016B	22	PB	GQ		2-10	24-41-11	D40540J	B09			SM00003		W		YC051-YD170
2016B	22	PB	GQ		2-11	24-41-11	D40540J	B09			SM00003		W		YL951-YR328
2016R	22	PB	GQ		0-0	24-41-11	D40540J	A09			SM00005		W		ALL
2017B	22	X2	GR		2-11	24-41-11	D40938J	B01			D10898A	39			ALL
2017R	22	X2	GR		0-0	24-41-11	D40938J	A01			D10898A	38			ALL
2017Z			GR		0-0	24-41-11	D40938J	DED			D10898A	DED			ALL

WIRE LIST

D280A108

91-21-11

Section W0420

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0422		286A0422			E4-2 SHELF (continued)											
2018B		20		PB	GS	3-1	24-41-11	D40382J		B06		D10898A		2		ALL
2018R		20		PB	GS	0-0	24-41-11	D40382J		A06		D10898A		1		ALL
2019B		22		PB	GT	3-5	24-22-21	D40472J		A01		D10892B		6		YC051-YD170
2019B		22		PB	GT	3-6	24-22-21	D40472J		A01		D10892B		6		YL951-YR328
2019R		22		PB	GT	0-0	24-22-21	D40472J		A02		D10892B		14		ALL
2409B		22		PB	OI	3-7	52-71-11	D40472J		A04		D40584J		B03		YC051-YD170
2409B		22		PB	OI	3-8	52-71-11	D40472J		A04		D40584J		B03		YL951-YR328
2409R		22		PB	OI	0-0	52-71-11	D40472J		A03		D40584J		A03		ALL
2419B		22		PB	OT	3-5	52-71-11	D40472J		A10		D40338J		B06		ALL
2419R		22		PB	OT	0-0	52-71-11	D40472J		A09		D40338J		A06		ALL
2444B		22		PB	PT	3-7	52-71-11	D40472J		A08		D40584J		B05		YC051-YD170
2444B		22		PB	PT	3-8	52-71-11	D40472J		A08		D40584J		B05		YL951-YR328
2444R		22		PB	PT	0-0	52-71-11	D40472J		A07		D40584J		A05		ALL
2458B		22		PB	QH	2-4	52-71-11	D40472J		A06		D40388J		B03		YC051-YD170
2458B		22		PB	QH	2-5	52-71-11	D40472J		A06		D40388J		B03		YL951-YR328
2458R		22		PB	QH	0-0	52-71-11	D40472J		A05		D40388J		B04		ALL
2601B		22		X2	SA	2-4	28-41-11	D40164J		A10		TB4201Y		A023	1A	ALL
2601R		22		X2	SA	0-0	28-41-11	D40164J		B10		TB4201Y		B023	1A	ALL
2601Z					SA	0-0	28-41-11	D40164J		PERG	1F	TB4201Y		A025	1A	ALL
2602B		22		X2	SB	3-2	28-41-11	TB4201Y		A023	1A	D40388J		A15		ALL
2602R		22		X2	SB	0-0	28-41-11	TB4201Y		B023	1A	D40388J		B15		ALL
2602Z					SB	0-0	28-41-11	TB4201Y		A025	1A	D40388J		PERG	1F	ALL
2603B		22		X2	SC	3-1	28-41-11	TB4201Y		A023	1A	D40618J		A04		YC051-YD170
2603B		22		X2	SC	3-2	28-41-11	TB4201Y		A023	1A	D40618J		A04		YL951-YR328
2603R		22		X2	SC	0-0	28-41-11	TB4201Y		B023	1A	D40618J		A05		ALL
2603Z					SC	0-0	28-41-11	TB4201Y		A025	1A	D40618J		PERG	1F	ALL
3001B		18		X3	WA	3-3	24-21-21	D40140J		G		D10892A		5		ALL
3001R		18		X3	WA	0-0	24-21-21	D40140J		H		D10892A		3		ALL
3001Y		18		X3	WA	0-0	24-21-21	D40140J		J		D10892A		4		ALL
3001Z					WA	0-0	24-21-21	D40140J		A10		GD04209		ST..	1A	ALL
3002B		22		PC	WB	3-6	24-22-21	D40540J		A06		D10892B		62		YC051-YD170
3002B		22		PC	WB	3-7	24-22-21	D40540J		A06		D10892B		62		YL951-YR328
3002R		22		PC	WB	0-0	24-22-21	D40540J		B05		D10892B		64		ALL
3002Y		22		PC	WB	0-0	24-22-21	D40540J		B06		D10892B		63		ALL
3003B		20		PC	WC	3-4	24-22-21	D40382J		B07		D10892A		36		ALL
3003R		20		PC	WC	0-0	24-22-21	D40382J		A07		D10892A		23		ALL
3003Y		20		PC	WC	0-0	24-22-21	D40382J		A08		D10892A		35		ALL
3004B		20		PC	WD	3-3	24-23-21	D40382J		A09		D10892B		53		ALL
3004R		20		PC	WD	0-0	24-23-21	D40382J		B08		D10892B		66		ALL

WIRE LIST

D280A108

91-21-11

Section W0420

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0422	286A0422			E4-2 SHELF (continued)											
3004Y	20	PC	WD		0-0	24-23-21	D40382J	B09			D10892B	54			ALL
3005B	22	PC	WE		3-4	24-41-11	D40540J	B10			D10898A	46			ALL
3005R	22	PC	WE		0-0	24-41-11	D40540J	A10			D10898A	59			ALL
3005Y	22	PC	WE		0-0	24-41-11	D40540J	A11			D10898A	58			ALL
3201B	20	PC	YA		2-11	28-23-11	D40938J	A05			D40714J	A05			ALL
3201R	20	PC	YA		0-0	28-23-11	D40938J	A03			D40714J	A03			ALL
3201Y	20	PC	YA		0-0	28-23-11	D40938J	A04			D40714J	A04			ALL
3202B	18	PC	YB		2-11	28-23-11	D40938J	J			D40714J	J			ALL
3202R	18	PC	YB		0-0	28-23-11	D40938J	G			D40714J	G			ALL
3202Y	18	PC	YB		0-0	28-23-11	D40938J	H			D40714J	H			ALL
3203B	20	PC	YC		2-11	28-23-11	D40938J	B05			D40714J	B05			ALL
3203R	20	PC	YC		0-0	28-23-11	D40938J	B03			D40714J	B03			ALL
3203Y	20	PC	YC		0-0	28-23-11	D40938J	B04			D40714J	B04			ALL
4001B	20	PD	A6		3-1	24-21-21	D40370J	B01			D10892A	16			ALL
4001G	20	PD	A6		0-0	24-21-21	D40370J	A02			D10892A	17			ALL
4001R	20	PD	A6		0-0	24-21-21	D40370J	A01			D10892A	7			ALL
4001Y	20	PD	A6		0-0	24-21-21	D40370J	B02			D10892A	15			ALL
4002B	22	PD	B6		3-3	24-24-21	D40140J	A03			D10892A	54			ALL
4002G	22	PD	B6		0-0	24-24-21	D40140J	B03			D10892A	53			ALL
4002R	22	PD	B6		0-0	24-24-21	D40140J	A04			D10892A	41			ALL
4002Y	22	PD	B6		0-0	24-24-21	D40140J	B04			D10892A	42			ALL
4003B	22	PD	C6		3-4	24-24-21	D40382J	B10			D10892A	51			ALL
4003G	22	PD	C6		0-0	24-24-21	D40382J	A11			D10892A	52			ALL
4003R	22	PD	C6		0-0	24-24-21	D40382J	A10			D10892A	38			ALL
4003Y	22	PD	C6		0-0	24-24-21	D40382J	B11			D10892A	39			ALL
4004B	22	PD	D6		2-10	24-41-11	D40370J	B03			D10898A	5			ALL
4004G	22	PD	D6		0-0	24-41-11	D40370J	A04			D10898A	13			ALL
4004R	22	PD	D6		0-0	24-41-11	D40370J	A03			D10898A	3			ALL
4004Y	22	PD	D6		0-0	24-41-11	D40370J	B04			D10898A	4			ALL
4005B	22	PD	E6		3-1	24-41-11	D40382J	B12			D10898A	16			ALL
4005G	22	PD	E6		0-0	24-41-11	D40382J	A13			D10898A	17			ALL
4005R	22	PD	E6		0-0	24-41-11	D40382J	A12			D10898A	7			ALL
4005Y	22	PD	E6		0-0	24-41-11	D40382J	B13			D10898A	15			ALL

WIRE LIST

D280A108

91-21-11
Section W0420
Page 13 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To			Effectivity				
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type		Splice	Equip	Term	Type
W0442	286A0442	AFT RIGHT HAND DOORWAY LINING													
0003	20	PA			1-11	33-51-14	D02986	1			D40046J	3			ALL
0004	20	PA			1-11	33-51-14	D02986	2			D40046J	4			ALL
0005	22	PA			2-6	33-26-11	L01302	=P	C		D40046J	5			ALL
0006	22	PA			2-6	33-26-11	L01302	=G	C		D40046J	6			ALL
2001B	22	PB	GA		2-11	23-31-04	M01213	COM	Z		D40046J	2			ALL
2001R	22	PB	GA		0-0	23-31-04	M01213	1K	Z		D40046J	1			YC051-YN260
2001R	22	PB	GA		0-0	23-31-04	M01213	2K	Z		D40046J	1			YN501-YR328
W0443	286A0443	CONTROL COLUMN-CAPT													
0001	20	PA			3-0	23-51-01	S00519	3	A		S00161	3	A		ALL
0001A	20	XN	AA		3-0	23-51-11	TB0806X	A002	1A		S00519	4	A		YC051-YD170
0001A	20	XN	AA		3-0	23-51-11	TB0806Y	A001	1A		S00519	4	A		YL951-YR328
0002K	20	XN	AA		0-0	SPARE	TB0806X	CAP	Y		S00742	=R1	*		ALL
0003KN	20	XN	AA		0-0	23-51-11	TB0806X	B002	1A		S00161	3	A		YC051-YD170
0003KN	20	XN	AA		0-0	23-51-11	TB0806Y	A003	1A		S00161	3	A		YL951-YR328
0004KA	20	XN	AA		0-0	22-14-11	TB0806Y	A011	1A		S00231	=KA	GS		ALL
0005B	20	XN	AA		0-0	22-14-11	TB0806Y	B011	1A		S00231	=B	GS		ALL
0006KR	20	XN	AA		0-0	23-51-11	TB0806X	A003	1A		S00161	4	A		YC051-YD170
0006KR	20	XN	AA		0-0	23-51-11	TB0806Y	B001	1A		S00161	4	A		YL951-YR328
0007Y	20	XN	AA		0-0	22-11-12	TB0806X	B013	1A		S00231	=Y	GS		ALL
0008G	20	XN	AA		0-0	22-11-12	TB0806X	A015	1A		S00231	=G	GS		ALL
0009O	20	XN	AA		0-0	27-41-11	TB0806Z	A021	1A		T00335	1	C		ALL
0010KO	20	XN	AA		0-0	27-41-11	TB0806Z	B017	1A		T00335	4	C		ALL
0011R	20	XN	AA		0-0	27-41-11	TB0806Y	A009	1A		T00335	3	C		ALL
0012V	20	XN	AA		0-0	27-41-11	TB0806Z	A017	1A		T00335	2	C		ALL
0013KG	20	XN	AA		0-0	33-11-11	TB0806V	A005	1		L00728	P	C		ALL
0014KY	20	XN	AA		0-0	33-11-11	GD05010	AC..	E		L00728	G	C		ALL
0015RN	20	XN	AA		0-0	SPARE	TB0806X	CAP	Y		S00742	=G1	*		ALL
0016ON	20	XN	AA		0-0	SPARE	TB0806X	CAP	Y		S00742	=G2	*		ALL
0017KB	20	XN	AA		0-0	22-11-12	TB0806X	A013	1A		S00231	=KB	GS		ALL
0018N	20	XN	AA		0-0	22-11-12	TB0806X	A014	1A		S00231	=N	GS		ALL
0019KV	20	XN	AA		0-0	SPARE	TB0806X	CAP	Y		S00742	=R2	*		ALL
0051	20	PA			3-0	SPARE	L00728	CAP	Y		L00728	CAP	Y		ALL
0052	20	PA			3-0	SPARE	L00728	CAP	Y		L00728	CAP	Y		ALL
W0444	286A0444	CENTER OVERHEAD STOWAGE LIGHT													
0001	18	PA			2-5	33-22-32	D14448	B			D14404	B			YN501-YR328
0002	18	PA			2-5	33-22-32	D14448	C			D14404	C			YN501-YR328
0003	18	PA			2-5	33-22-32	D14448	A			D14404	A			YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0440

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W0444	286A0444	CENTER OVERHEAD STOWAGE LIGHT (continued)													
2001B	24	OT	EA	2-4	33-22-32	D14682		2	D14684	2				YN501-YR328	
2001W	24	OT	EA	0-0	33-22-32	D14682		1	D14684	1				YN501-YR328	
2001Z			EA	0-0	33-22-32	D14682		5	D14684	5				YN501-YR328	
2002B	24	PL	EB	2-4	33-22-32	D14682		4	D14684	4				YN501-YR328	
2002R	24	PL	EB	0-0	33-22-32	D14682		3	D14684	3				YN501-YR328	
2003B	24	OT	EC	6-9	33-22-32	D14686		2	D14688	2				YN501-YR328	
2003W	24	OT	EC	0-0	33-22-32	D14686		1	D14688	1				YN501-YR328	
2003Z			EC	0-0	33-22-32	D14686		5	D14688	5				YN501-YR328	
2004B	24	PL	ED	6-9	33-22-32	D14686		4	D14688	4				YN501-YR328	
2004R	24	PL	ED	0-0	33-22-32	D14686		3	D14688	3				YN501-YR328	
W0445	286A0445	CONTROL COLUMN-F/O													
0002	20	PA		3-0	23-51-02	S00520		3	A	S00214	3	A	*	ALL	
0021A	20	XN	AA	3-0	23-51-21	TB0805X		A002	1A	S00520	4	A		ALL	
0022K	20	XN	AA	0-0	SPARE	TB0805X		CAP	Y	S00743	=R1	*		ALL	
0023KN	20	XN	AA	0-0	23-51-21	TB0805X		B002	1A	S00214	3	A		YC051-YD170	
0023KN	20	XN	AA	0-0	23-51-21	TB0805Y		B011	1A	S00214	3	A	*	YL951-YR328	
0024KA	20	XN	AA	0-0	22-14-11	TB0805X		A016	1A	S00232	=KA	GS		ALL	
0025B	20	XN	AA	0-0	22-14-11	TB0805X		B016	1A	S00232	=B	GS		ALL	
0026KR	20	XN	AA	0-0	23-51-21	TB0805X		A003	1A	S00214	4	A		YC051-YD170	
0026KR	20	XN	AA	0-0	23-51-21	TB0805Y		A011	1A	S00214	4	A		YL951-YR328	
0027Y	20	XN	AA	0-0	22-11-12	TB0805Y		A009	1A	S00232	=Y	GS		ALL	
0028G	20	XN	AA	0-0	22-11-12	TB0805X		B015	1A	S00232	=G	GS		ALL	
0029O	20	XN	AA	0-0	27-41-11	TB0805X		B004	1A	T00336	1	C		ALL	
0030KO	20	XN	AA	0-0	27-41-11	TB0805X		A004	1A	T00336	4	C		ALL	
0031R	20	XN	AA	0-0	27-41-11	TB0805X		A001	1A	T00336	3	C		ALL	
0032V	20	XN	AA	0-0	27-41-11	TB0805X		B001	1A	T00336	2	C		ALL	
0033KG	20	XN	AA	0-0	33-11-21	TB0805V		A005	1	L00729	P	C		ALL	
0034KY	20	XN	AA	0-0	33-11-21	GD00475		AC..	E	L00729	G	C		ALL	
0035RN	20	XN	AA	0-0	SPARE	TB0805X		CAP	Y	S00743	=G1	*		ALL	
0036ON	20	XN	AA	0-0	SPARE	TB0805		CAP	Y	S00743	=G2	*		ALL	
0037KB	20	XN	AA	0-0	22-11-12	TB0805Y		B009	1A	S00232	=KB	GS		ALL	
0038N	20	XN	AA	0-0	22-11-12	TB0805X		B014	1A	S00232	=N	GS		ALL	
0039KV	20	XN	AA	0-0	SPARE	TB0805		CAP	Y	S00743	=R2	*		ALL	
0061	20	PA		3-0	SPARE	L00729		CAP	Y	L00729	CAP	Y		ALL	
0062	20	PA		3-0	SPARE	L00729		CAP	Y	L00729	CAP	Y		ALL	
W0446	286A0446	CENTER OVERHEAD STOWAGE LIGHT - LEFT FWD													
0001	18	PA		2-4	33-22-21	D14746		B	D14748	B				YN501-YR328	

WIRE LIST

D280A108

91-21-11

Section W0440

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity

W0446		286A0446			CENTER OVERHEAD STOWAGE LIGHT - LEFT FWD (continued)											
0002		18		PA		2-4	33-22-21	D14746		C		D14748		C		YN501-YR328
0003		18		PA		2-4	33-22-21	D14746		A		D14748		A		YN501-YR328
2001B		24		OT	EA	2-4	33-22-21	D14742		2		D14744		2		YN501-YR328
2001W		24		OT	EA	0-0	33-22-21	D14742		1		D14744		1		YN501-YR328
2001Z					EA	0-0	33-22-21	D14742		5		D14744		5		YN501-YR328
2002B		24		PL	EB	2-4	33-22-21	D14742		4		D14744		4		YN501-YR328
2002R		24		PL	EB	0-0	33-22-21	D14742		3		D14744		3		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0440

Page 3 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0452	286A0452			AFT LEFT HAND DOORWAY LINING											
0003	20	PA		2-2	33-51-14	D40044J		3			D02982	1			ALL
0004	20	PA		2-2	33-51-14	D40044J		4			D02982	2			ALL
0005	22	PA		2-7	33-26-11	D40044J		5			L01303	=P	C		ALL
0006	22	PA		2-7	33-26-11	D40044J		6			L01303	=G	C		ALL
2001B	22	PB	GA	3-2	23-31-04	M01212		COM	Z		D40044J	2			ALL
2001R	22	PB	GA	0-0	23-31-04	M01212		1K	Z		D40044J	1			YC051-YN260
2001R	22	PB	GA	0-0	23-31-04	M01212		2K	Z		D40044J	1			YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0450

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521		286A0521					E5-2 SHELF WIRE BUNDLE #1									
0001		20		GA		6-3	34-61-11	D02179C		1		D45245P	B13			YC051-YC052
0001		20		CQ		7-0	34-61-11	D02179C		1		D45209P	A08			YC053-YC058
0001		20		CQ		7-3	34-61-11	D02179C		1		D45209P	A08			YC059-YR328
0002		20		GA		3-7	34-61-11	D45245P		B14		SM00041		W		YC051-YC052
0002		20		CQ		4-3	34-61-11	D45209P		A09		SM00041		W		YC053-YC058
0002		20		CQ		4-9	34-61-11	D45209P		A09		SM00041		W		YC059-YR328
0003		20		PA		1-11	34-61-11	D02179C		7		GD05220	AC..	E		ALL
0004		20		PA		1-7	34-61-11	D02179C		8		GD05213	DC..	E	*2	ALL
0005		22		PA		4-1	34-61-11	D05925P		A02		SM00052		W		YC051-YC058
0005		22		PA		4-4	34-61-11	D05925P		A02		SM00052		W		YC059-YR328
0006		22		PA		1-11	34-61-11	D02179B		F06		SM00052		W		ALL
0007		22		PA		1-3	34-61-11	D03261B		F06		SM00052		W		ALL
0008		22		PA		3-0	34-61-12	D03265		M-		GD05209	DC..	E	*1	YC051-YC058
0008		22		PA		3-3	34-61-12	D03265		M-		GD05209	DC..	E	*1	YC059-YR328
0009		22		PA		7-2	34-61-12	D03265		P-		D45235P	A02			YC051-YC058
0009		22		PA		7-8	34-61-12	D03265		P-		D45235P	A02			YC059-YD157
0009		22		PA		7-8	34-61-12	D45235P		A02		D03265		P-		YD158-YR328
0010		22		PA		7-4	34-61-12	D03265		Q-		D45255P	B11			YC051-YC058
0010		22		PA		7-10	34-61-12	D03265		Q-		D45255P	B11			YC059-YR328
0011		22		PA		2-1	34-61-12	D03265		N-		D03423		T-		YC051-YC058
0011		22		PA		2-7	34-61-12	D03265		N-		D03423		T-		YC059-YR328
0012		22		PA		3-0	34-61-12	D03265		E-		GD05209	DC..	E	*1	YC051-YC058
0012		22		PA		3-3	34-61-12	D03265		E-		GD05209	DC..	E	*1	YC059-YR328
0013		22		PA		7-4	34-61-12	D03267		T-		D45235P	A03			YC051-YC058
0013		22		PA		7-10	34-61-12	D03267		T-		D45235P	A03			YC059-YD157
0013		22		PA		7-10	34-61-12	D45235P		A03		D03267		T-		YD158-YR328
0014		22		PA		8-4	34-61-12	D03267		Z		D45221P	B10			YC051-YC058
0014		22		PA		8-10	34-61-12	D03267		Z		D45221P	B10			YC059-YR328
0015		22		PA		2-0	34-61-12	D03263		T-		D03425		N-		YC051-YC058
0015		22		PA		2-6	34-61-12	D03263		T-		D03425		N-		YC059-YR328
0016		22		PA		2-10	34-61-12	D03263		Z		GD05209	DC..	E		YC051-YC058
0016		22		PA		3-1	34-61-12	D03263		Z		GD05209	DC..	E	*3	YC059-YR328
0017		22		PA		8-1	34-61-12	D03263		E-		D45221P	B07			YC051-YC058
0017		22		PA		8-7	34-61-12	D03263		E-		D45221P	B07			YC059-YR328
0018		22		PA		3-3	34-61-12	D45255P		B13		D45221P	B08			YC051-YC058
0018		22		PA		3-9	34-61-12	D45255P		B13		D45221P	B08			YC059-YR328
0019		22		PA		2-0	34-61-12	D45255P		B14		SM00054		W		YC051-YC058
0019		22		PA		2-6	34-61-12	D45255P		B14		SM00054		W		YC059-YR328
0020		22		PA		1-11	34-61-12	D41561P		A14		SM00054		W		YC051-YC058

WIRE LIST

D280A108

91-21-11

Section W0520

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521	286A0521				E5-2 SHELF WIRE BUNDLE #1 (continued)										
0020	22		PA		2-5	34-61-12	D41561P	A14			SM00054		W		YC059-YR328
0021	22		PA		2-10	34-61-12	D45221P	B06			SM00054		W		YC051-YC058
0021	22		PA		3-4	34-61-12	D45221P	B06			SM00054		W		YC059-YR328
0022	22		PA		5-5	34-61-12	D45221P	B11			SM00055		W		YC051-YC058
0022	22		PA		6-2	34-61-12	D45221P	B11			SM00055		W		YC059-YR328
0023	22		PA		5-5	34-61-12	D45221P	B13			SM00056		W		YC051-YC058
0023	22		PA		6-2	34-61-12	D45221P	B13			SM00056		W		YC059-YR328
0024	22		PA		7-3	34-61-16	D45245P	A07			D03263	X			YC051-YC058
0024	22		PA		7-9	34-61-16	D45245P	A07			D03263	X			YC059-YR328
0025	22		PA		7-3	34-61-16	D45245P	A08			D03263	Y			YC051-YC058
0025	22		PA		7-9	34-61-16	D45245P	A08			D03263	Y			YC059-YR328
0026	22		PA		1-10	34-61-16	D03425	F			SM00057		W		YC051-YC058
0026	22		PA		2-1	34-61-16	D03425	F			SM00057		W		YC059-YR328
0027	22		PA		1-5	34-61-16	D02179B	K07			SM00057		W		ALL
0028	22		PA		2-7	34-61-16	D03267	Y			SM00057		W		YC051-YC058
0028	22		PA		2-10	34-61-16	D03267	Y			SM00057		W		YC059-YR328
0029	22		PA		3-7	34-61-16	D02179A	K13			D03267	X			YC051-YC058
0029	22		PA		3-10	34-61-16	D02179A	K13			D03267	X			YC059-YR328
0030	24		PK		3-0	34-61-17	D45235P	A06			SM00001		W		YC051-YC058
0030	24		PK		3-6	34-61-17	D45235P	A06			SM00001		W		YC059-YR328
0031	24		PK		3-3	34-61-17	D02179B	G13			SM00001		W		YC051-YC058
0031	24		PK		3-6	34-61-17	D02179B	G13			SM00001		W		YC059-YR328
0032	24		PK		3-0	34-61-17	D45235P	A07			SM00002		W		YC051-YC058
0032	24		PK		3-6	34-61-17	D45235P	A07			SM00002		W		YC059-YR328
0033	24		PK		3-3	34-61-17	D02179B	F13			SM00002		W		YC051-YC058
0033	24		PK		3-6	34-61-17	D02179B	F13			SM00002		W		YC059-YR328
0034	24		PK		1-8	34-61-17	D45235P	A08			SM00003		W		YC051-YC058
0034	24		PK		2-4	34-61-17	D45235P	A08			SM00003		W		YC059-YR328
0035	24		PK		4-7	34-61-17	D02179B	J14			SM00003		W		YC051-YC058
0035	24		PK		4-8	34-61-17	D02179B	J14			SM00003		W		YC059-YR328
0036	24		PK		1-8	34-61-17	D45235P	A09			SM00004		W		YC051-YC058
0036	24		PK		2-4	34-61-17	D45235P	A09			SM00004		W		YC059-YR328
0037	24		PK		4-7	34-61-17	D02179B	H13			SM00004		W		YC051-YC058
0037	24		PK		4-8	34-61-17	D02179B	H13			SM00004		W		YC059-YR328
0038	24		PK		1-8	34-61-17	D45235P	A10			SM00005		W		YC051-YC058
0038	24		PK		2-4	34-61-17	D45235P	A10			SM00005		W		YC059-YR328
0039	24		PK		4-7	34-61-17	D02179B	H14			SM00005		W		YC051-YC058
0039	24		PK		4-8	34-61-17	D02179B	H14			SM00005		W		YC059-YR328
0040	24		PK		1-9	34-61-17	D41561P	A09			SM00006		W		YC051-YC058

WIRE LIST

D280A108

91-21-11

Section W0520

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521		286A0521			E5-2 SHELF WIRE BUNDLE #1 (continued)											
0040		24		PK		2-5	34-61-17	D41561P	A09			SM00006		W		YC059-YR328
0041		24		PK		4-7	34-61-17	D02179B	J13			SM00006		W		YC051-YC058
0041		24		PK		4-8	34-61-17	D02179B	J13			SM00006		W		YC059-YR328
0042		24		PK		1-9	34-61-17	D41561P	A10			SM00007		W		YC051-YC058
0042		24		PK		2-5	34-61-17	D41561P	A10			SM00007		W		YC059-YR328
0043		24		PK		4-7	34-61-17	D02179B	B14			SM00007		W		YC051-YC058
0043		24		PK		4-8	34-61-17	D02179B	B14			SM00007		W		YC059-YR328
0044		24		PK		1-9	34-61-17	D41561P	A17			SM00008		W		YC051-YC058
0044		24		PK		2-5	34-61-17	D41561P	A17			SM00008		W		YC059-YR328
0045		24		PK		4-7	34-61-17	D02179B	A14			SM00008		W		YC051-YC058
0045		24		PK		4-8	34-61-17	D02179B	A14			SM00008		W		YC059-YR328
0046		24		PK		1-9	34-61-17	D41561P	A18			SM00009		W		YC051-YC058
0046		24		PK		2-5	34-61-17	D41561P	A18			SM00009		W		YC059-YR328
0047		24		PK		4-7	34-61-17	D02179B	C14			SM00009		W		YC051-YC058
0047		24		PK		4-8	34-61-17	D02179B	C14			SM00009		W		YC059-YR328
0048		24		PK		1-9	34-61-17	D41561P	A19			SM00010		W		YC051-YC058
0048		24		PK		2-5	34-61-17	D41561P	A19			SM00010		W		YC059-YR328
0049		24		PK		4-7	34-61-17	D02179B	K04			SM00010		W		YC051-YC058
0049		24		PK		4-8	34-61-17	D02179B	K04			SM00010		W		YC059-YR328
0050		24		PK		3-11	34-61-17	D03261B	K04			SM00010		W		YC051-YC058
0050		24		PK		4-1	34-61-17	D03261B	K04			SM00010		W		YC059-YR328
0051		24		PK		3-11	34-61-17	D03261B	C14			SM00009		W		YC051-YC058
0051		24		PK		4-1	34-61-17	D03261B	C14			SM00009		W		YC059-YR328
0052		24		PK		3-11	34-61-17	D03261B	A14			SM00008		W		YC051-YC058
0052		24		PK		4-1	34-61-17	D03261B	A14			SM00008		W		YC059-YR328
0053		24		PK		3-11	34-61-17	D03261B	B14			SM00007		W		YC051-YC058
0053		24		PK		4-1	34-61-17	D03261B	B14			SM00007		W		YC059-YR328
0054		24		PK		3-11	34-61-17	D03261B	J13			SM00006		W		YC051-YC058
0054		24		PK		4-1	34-61-17	D03261B	J13			SM00006		W		YC059-YR328
0055		24		PK		3-11	34-61-17	D03261B	H14			SM00005		W		YC051-YC058
0055		24		PK		4-1	34-61-17	D03261B	H14			SM00005		W		YC059-YR328
0056		24		PK		3-11	34-61-17	D03261B	H13			SM00004		W		YC051-YC058
0056		24		PK		4-1	34-61-17	D03261B	H13			SM00004		W		YC059-YR328
0057		24		PK		3-11	34-61-17	D03261B	J14			SM00003		W		YC051-YC058
0057		24		PK		4-1	34-61-17	D03261B	J14			SM00003		W		YC059-YR328
0058		24		PK		2-7	34-61-17	D03261B	F13			SM00002		W		YC051-YC058
0058		24		PK		2-10	34-61-17	D03261B	F13			SM00002		W		YC059-YR328
0059		24		PK		2-7	34-61-17	D03261B	G13			SM00001		W		YC051-YC058
0059		24		PK		2-10	34-61-17	D03261B	G13			SM00001		W		YC059-YR328

WIRE LIST

D280A108

91-21-11

Section W0520

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number		Fam	Description		Diagram	From			To			Effectivity		
	GA	CO TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W0521	286A0521			E5-2 SHELF WIRE BUNDLE #1 (continued)											
0060	24	PK		1-4	34-61-17	D03261A		K01		SM00038		W		ALL	
0061	24	PK		2-1	31-62-15	D45225P		A18		D45245P	A10			YC051-YC058	
0061	24	PK		2-7	31-62-15	D45225P		A18		D45245P	A10			YC059-YR328	
0062	22	PA		6-10	34-61-18	D45225P		A10		D03263	A-			YC051-YC058	
0063	22	PA		6-10	34-61-18	D45225P		A09		D03263	B-			YC051-YC058	
0064	22	PA		1-9	34-61-19	D02179B		K01		GD05213	DC..	E	*1	ALL	
0065	22	PA		1-9	34-61-19	D02179B		K05		GD05213	DC..	E	*1	ALL	
0066	22	PA		3-3	34-61-19	D02179B		C11		SM00011		W		YC051-YC058	
0066	22	PA		3-6	34-61-19	D02179B		C11		SM00011		W		YC059-YR328	
0067	22	PA		3-3	34-61-19	D02179B		D11		SM00012		W		YC051-YC058	
0067	22	PA		3-6	34-61-19	D02179B		D11		SM00012		W		YC059-YR328	
0068	22	PA		3-3	34-61-19	D02179B		E11		SM00013		W		YC051-YC058	
0068	22	PA		3-6	34-61-19	D02179B		E11		SM00013		W		YC059-YR328	
0069	22	PA		3-3	34-61-19	D02179B		F11		SM00014		W		YC051-YC058	
0069	22	PA		3-6	34-61-19	D02179B		F11		SM00014		W		YC059-YR328	
0070	22	PA		3-3	34-61-19	D02179B		G11		SM00015		W		YC051-YC058	
0070	22	PA		3-6	34-61-19	D02179B		G11		SM00015		W		YC059-YR328	
0071	22	PA		3-3	34-61-19	D02179B		H11		SM00016		W		YC051-YC058	
0071	22	PA		3-6	34-61-19	D02179B		H11		SM00016		W		YC059-YR328	
0072	22	PA		3-1	34-61-19	D02179B		A12		SM00017		W		YC051-YL954, YN231-YN235	
0072	22	PA		3-4	34-61-19	D02179B		A12		SM00017		W		YL955-YL999, YN236-YR328	
0073	22	PA		3-1	34-61-19	D02179B		B12		SM00018		W		YC051-YL954, YN231-YN235	
0073	22	PA		3-4	34-61-19	D02179B		B12		SM00018		W		YL955-YL999, YN236-YR328	
0074	22	PA		3-1	34-61-19	D02179B		F14		SM00019		W		YC051-YL954, YN231-YN235	
0074	22	PA		3-4	34-61-19	D02179B		F14		SM00019		W		YL955-YL999, YN236-YR328	
0075	22	PA		3-1	34-61-19	D02179B		F15		SM00020		W		YC051-YL954, YN231-YN235	
0075	22	PA		3-4	34-61-19	D02179B		F15		SM00020		W		YL955-YL999, YN236-YR328	
0076	22	PA		2-7	34-61-19	D03261B		C11		SM00011		W		YC051-YC058	
0076	22	PA		2-10	34-61-19	D03261B		C11		SM00011		W		YC059-YR328	
0077	22	PA		2-7	34-61-19	D03261B		D11		SM00012		W		YC051-YC058	
0077	22	PA		2-10	34-61-19	D03261B		D11		SM00012		W		YC059-YR328	

WIRE LIST

D280A108

91-21-11

Section W0520

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521	286A0521			E5-2 SHELF WIRE BUNDLE #1 (continued)											
0078	22		PA		2-7	34-61-19	D03261B	E11			SM00013		W		YC051-YC058
0078	22		PA		2-10	34-61-19	D03261B	E11			SM00013		W		YC059-YR328
0079	22		PA		2-7	34-61-19	D03261B	F11			SM00014		W		YC051-YC058
0079	22		PA		2-10	34-61-19	D03261B	F11			SM00014		W		YC059-YR328
0080	22		PA		2-7	34-61-19	D03261B	G11			SM00015		W		YC051-YC058
0080	22		PA		2-10	34-61-19	D03261B	G11			SM00015		W		YC059-YR328
0081	22		PA		2-7	34-61-19	D03261B	H11			SM00016		W		YC051-YC058
0081	22		PA		2-10	34-61-19	D03261B	H11			SM00016		W		YC059-YR328
0082	22		PA		2-5	34-61-19	D03261B	A12			SM00017		W		YC051-YC058
0082	22		PA		2-6	34-61-19	D03261B	A12			SM00017		W		YC059-YL954, YN231-YN235
0082	22		PA		2-8	34-61-19	D03261B	A12			SM00017		W		YL955-YL999, YN236-YR328
0083	22		PA		2-5	34-61-19	D03261B	B12			SM00018		W		YC051-YC058
0083	22		PA		2-6	34-61-19	D03261B	B12			SM00018		W		YC059-YL954, YN231-YN235
0083	22		PA		2-8	34-61-19	D03261B	B12			SM00018		W		YL955-YL999, YN236-YR328
0084	22		PA		2-5	34-61-19	D03261B	F14			SM00019		W		YC051-YC058
0084	22		PA		2-6	34-61-19	D03261B	F14			SM00019		W		YC059-YL954, YN231-YN235
0084	22		PA		2-8	34-61-19	D03261B	F14			SM00019		W		YL955-YL999, YN236-YR328
0085	22		PA		2-5	34-61-19	D03261B	F15			SM00020		W		YC051-YC058
0085	22		PA		2-6	34-61-19	D03261B	F15			SM00020		W		YC059-YL954, YN231-YN235
0085	22		PA		2-8	34-61-19	D03261B	F15			SM00020		W		YL955-YL999, YN236-YR328
0086	22		PA		6-7	34-61-19	D03261B	K01			D45221P	A11			YC051-YC058
0086	22		PA		6-10	34-61-19	D03261B	K01			D45221P	A11			YC059-YR328
0087	22		PA		6-7	34-61-19	D03261B	K03			D45221P	A12			YC051-YC058
0087	22		PA		6-10	34-61-19	D03261B	K03			D45221P	A12			YC059-YR328
0088	22		PA		2-2	34-61-19	D03261B	K05			GD05213	DC..	E	*2	ALL
0089	22		PA		4-1	34-61-19	D45221P	A01			SM00011		W		YC051-YC058
0089	22		PA		4-7	34-61-19	D45221P	A01			SM00011		W		YC059-YR328
0090	22		PA		4-1	34-61-19	D45221P	A02			SM00012		W		YC051-YC058
0090	22		PA		4-7	34-61-19	D45221P	A02			SM00012		W		YC059-YR328
0091	22		PA		4-1	34-61-19	D45221P	A03			SM00013		W		YC051-YC058
0091	22		PA		4-7	34-61-19	D45221P	A03			SM00013		W		YC059-YR328

WIRE LIST

D280A108

91-21-11

Section W0520

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521	286A0521			E5-2 SHELF WIRE BUNDLE #1 (continued)											
0092	22		PA		4-1	34-61-19	D45221P		A04		SM00014		W		YC051-YC058
0092	22		PA		4-7	34-61-19	D45221P		A04		SM00014		W		YC059-YR328
0093	22		PA		4-1	34-61-19	D45221P		A05		SM00015		W		YC051-YC058
0093	22		PA		4-7	34-61-19	D45221P		A05		SM00015		W		YC059-YR328
0094	22		PA		4-1	34-61-19	D45221P		A06		SM00016		W		YC051-YC058
0094	22		PA		4-7	34-61-19	D45221P		A06		SM00016		W		YC059-YR328
0095	22		PA		4-3	34-61-19	D45221P		A07		SM00017		W		YC051-YC058
0095	22		PA		4-5	34-61-19	D45221P		A07		SM00017		W		YC059-YL954, YN231-YN235
0095	22		PA		4-9	34-61-19	D45221P		A07		SM00017		W		YL955-YL999, YN236-YR328
0096	22		PA		4-3	34-61-19	D45221P		A08		SM00018		W		YC051-YC058
0096	22		PA		4-5	34-61-19	D45221P		A08		SM00018		W		YC059-YL954, YN231-YN235
0096	22		PA		4-9	34-61-19	D45221P		A08		SM00018		W		YL955-YL999, YN236-YR328
0097	22		PA		4-3	34-61-19	D45221P		A09		SM00019		W		YC051-YC058
0097	22		PA		4-5	34-61-19	D45221P		A09		SM00019		W		YC059-YL954, YN231-YN235
0097	22		PA		4-9	34-61-19	D45221P		A09		SM00019		W		YL955-YL999, YN236-YR328
0098	22		PA		4-3	34-61-19	D45221P		A10		SM00020		W		YC051-YC058
0098	22		PA		4-5	34-61-19	D45221P		A10		SM00020		W		YC059-YL954, YN231-YN235
0098	22		PA		4-9	34-61-19	D45221P		A10		SM00020		W		YL955-YL999, YN236-YR328
0099	22		PA		3-1	34-61-19	D02179B		A10		SM00021		W		YC051-YL954, YN231-YN235
0099	22		PA		3-4	34-61-19	D02179B		A10		SM00021		W		YL955-YL999, YN236-YR328
0101	22		PA		3-1	34-61-19	D02179B		C10		SM00023		W		YC051-YL954, YN231-YN235
0101	22		PA		3-4	34-61-19	D02179B		C10		SM00023		W		YL955-YL999, YN236-YR328
0102	22		PA		3-1	34-61-19	D02179B		D10		SM00024		W		YC051-YL954, YN231-YN235
0102	22		PA		3-4	34-61-19	D02179B		D10		SM00024		W		YL955-YL999, YN236-YR328
0103	22		PA		3-0	34-61-19	D02179B		F10		SM00025		W		YC051-YC058

WIRE LIST

D280A108

91-21-11

Section W0520

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521	286A0521			E5-2 SHELF WIRE BUNDLE #1 (continued)											
0103	22		PA		3-3	34-61-19	D02179B	F10			SM00025		W		YC059-YR328
0104	22		PA		3-0	34-61-19	D02179B	G10			SM00026		W		YC051-YC058
0104	22		PA		3-3	34-61-19	D02179B	G10			SM00026		W		YC059-YR328
0105	22		PA		3-0	34-61-19	D02179B	H10			SM00027		W		YC051-YC058
0105	22		PA		3-3	34-61-19	D02179B	H10			SM00027		W		YC059-YR328
0106	22		PA		3-0	34-61-19	D02179B	J10			SM00028		W		YC051-YC058
0106	22		PA		3-3	34-61-19	D02179B	J10			SM00028		W		YC059-YR328
0107	22		PA		3-0	34-61-19	D02179B	F12			SM00029		W		YC051-YC058
0107	22		PA		3-3	34-61-19	D02179B	F12			SM00029		W		YC059-YR328
0108	22		PA		3-0	34-61-19	D02179B	H12			SM00030		W		YC051-YC058
0108	22		PA		3-3	34-61-19	D02179B	H12			SM00030		W		YC059-YR328
0109	22		PA		3-0	34-61-19	D02179B	B13			SM00031		W		YC051-YC058
0109	22		PA		3-3	34-61-19	D02179B	B13			SM00031		W		YC059-YR328
0110	22		PA		3-0	34-61-19	D02179B	C13			SM00032		W		YC051-YC058
0110	22		PA		3-3	34-61-19	D02179B	C13			SM00032		W		YC059-YR328
0112	22		PA		2-5	34-61-19	D03261B	A10			SM00021		W		YC051-YC058
0112	22		PA		2-6	34-61-19	D03261B	A10			SM00021		W		YC059-YL954, YN231-YN235
0112	22		PA		2-8	34-61-19	D03261B	A10			SM00021		W		YL955-YL999, YN236-YR328
0114	22		PA		2-5	34-61-19	D03261B	C10			SM00023		W		YC051-YC058
0114	22		PA		2-6	34-61-19	D03261B	C10			SM00023		W		YC059-YL954, YN231-YN235
0114	22		PA		2-8	34-61-19	D03261B	C10			SM00023		W		YL955-YL999, YN236-YR328
0115	22		PA		2-5	34-61-19	D03261B	D10			SM00024		W		YC051-YC058
0115	22		PA		2-6	34-61-19	D03261B	D10			SM00024		W		YC059-YL954, YN231-YN235
0115	22		PA		2-8	34-61-19	D03261B	D10			SM00024		W		YL955-YL999, YN236-YR328
0116	22		PA		2-4	34-61-19	D03261B	F10			SM00025		W		YC051-YC058
0116	22		PA		2-7	34-61-19	D03261B	F10			SM00025		W		YC059-YR328
0117	22		PA		2-4	34-61-19	D03261B	G10			SM00026		W		YC051-YC058
0117	22		PA		2-7	34-61-19	D03261B	G10			SM00026		W		YC059-YR328
0118	22		PA		2-4	34-61-19	D03261B	H10			SM00027		W		YC051-YC058
0118	22		PA		2-7	34-61-19	D03261B	H10			SM00027		W		YC059-YR328
0119	22		PA		2-4	34-61-19	D03261B	J10			SM00028		W		YC051-YC058
0119	22		PA		2-7	34-61-19	D03261B	J10			SM00028		W		YC059-YR328
0120	22		PA		2-4	34-61-19	D03261B	F12			SM00029		W		YC051-YC058

WIRE LIST

D280A108

91-21-11

Section W0520

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W0521	286A0521				E5-2 SHELF WIRE BUNDLE #1 (continued)											
0120	22		PA		2-7	34-61-19		D03261B	F12			SM00029		W		YC059-YR328
0121	22		PA		2-4	34-61-19		D03261B	H12			SM00030		W		YC051-YC058
0121	22		PA		2-7	34-61-19		D03261B	H12			SM00030		W		YC059-YR328
0122	22		PA		2-4	34-61-19		D03261B	B13			SM00031		W		YC051-YC058
0122	22		PA		2-7	34-61-19		D03261B	B13			SM00031		W		YC059-YR328
0123	22		PA		2-4	34-61-19		D03261B	C13			SM00032		W		YC051-YC058
0123	22		PA		2-7	34-61-19		D03261B	C13			SM00032		W		YC059-YR328
0125	22		PA		4-3	34-61-19		D45221P	A13			SM00021		W		YC051-YC058
0125	22		PA		4-5	34-61-19		D45221P	A13			SM00021		W		YC059-YL954, YN231-YN235
0125	22		PA		4-9	34-61-19		D45221P	A13			SM00021		W		YL955-YL999, YN236-YR328
0127	22		PA		4-3	34-61-19		D45221P	A15			SM00023		W		YC051-YC058
0127	22		PA		4-5	34-61-19		D45221P	A15			SM00023		W		YC059-YL954, YN231-YN235
0127	22		PA		4-9	34-61-19		D45221P	A15			SM00023		W		YL955-YL999, YN236-YR328
0128	22		PA		4-3	34-61-19		D45221P	A16			SM00024		W		YC051-YC058
0128	22		PA		4-5	34-61-19		D45221P	A16			SM00024		W		YC059-YL954, YN231-YN235
0128	22		PA		4-9	34-61-19		D45221P	A16			SM00024		W		YL955-YL999, YN236-YR328
0129	22		PA		4-4	34-61-19		D45221P	A17			SM00025		W		YC051-YC058
0129	22		PA		4-10	34-61-19		D45221P	A17			SM00025		W		YC059-YR328
0130	22		PA		4-4	34-61-19		D45221P	A18			SM00026		W		YC051-YC058
0130	22		PA		4-10	34-61-19		D45221P	A18			SM00026		W		YC059-YR328
0131	22		PA		4-4	34-61-19		D45221P	A19			SM00027		W		YC051-YC058
0131	22		PA		4-10	34-61-19		D45221P	A19			SM00027		W		YC059-YR328
0132	22		PA		4-4	34-61-19		D45221P	A20			SM00028		W		YC051-YC058
0132	22		PA		4-10	34-61-19		D45221P	A20			SM00028		W		YC059-YR328
0133	22		PA		4-4	34-61-19		D45221P	B01			SM00029		W		YC051-YC058
0133	22		PA		4-10	34-61-19		D45221P	B01			SM00029		W		YC059-YR328
0134	22		PA		4-4	34-61-19		D45221P	B02			SM00030		W		YC051-YC058
0134	22		PA		4-10	34-61-19		D45221P	B02			SM00030		W		YC059-YR328
0135	22		PA		4-4	34-61-19		D45221P	B03			SM00031		W		YC051-YC058
0135	22		PA		4-10	34-61-19		D45221P	B03			SM00031		W		YC059-YR328
0136	22		PA		4-4	34-61-19		D45221P	B04			SM00032		W		YC051-YC058
0136	22		PA		4-10	34-61-19		D45221P	B04			SM00032		W		YC059-YR328
0138	22		PA		3-7	34-61-18		D02179A	F09			D03267	A-			YC051-YC058

WIRE LIST

D280A108

91-21-11

Section W0520

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521		286A0521			E5-2 SHELF WIRE BUNDLE #1 (continued)											
0139		22		PA		3-5	34-61-18	D02179B	A11			D03267	B-			YC051-YC058
0139		24		PK		6-2	34-61-18	D02179B	A11			D45293P	A03			YC059-YR328
0140		20		CQ		7-4	34-21-11	D03687C	1			D45209P	A02			YC051-YC058
0140		20		CQ		7-7	34-21-11	D03687C	1			D45209P	A02			YC059-YR328
0141		20		CQ		1-6	34-21-11	D03687C	5			GD05220	AC..	E		ALL
0142		20		PA		2-2	34-21-11	D03687C	11			GD05210	ST..	E		ALL
0143		20		PA		2-10	34-21-11	D45209P	A04			SM00049		W		YC051-YC058
0143		20		PA		3-4	34-21-11	D45209P	A04			SM00049		W		YC059-YD170
0143		20		CQ		3-4	34-21-11	D45209P	A04			SM00049		W		YL951-YR328
0144		20		CQ		4-7	34-21-11	D03687C	10			SM00049		W		YC051-YC058
0144		20		CQ		4-10	34-21-11	D03687C	10			SM00049		W		YC059-YR328
0145		20		CQ		1-6	34-21-11	D03687C	4			GD05220	AC..	E		ALL
0146		20		CQ		1-11	34-21-11	D03687C	8			GD05213	DC..	E		ALL
0147		24		PK		2-3	23-27-11	D45225P	B17			D45211P	A01			YC051-YC058
0147		24		PK		2-9	23-27-11	D45225P	B17			D45211P	A01			YC059-YD157,
0147		24		PK		2-9	23-27-39	D45225P	B17			D45211P	A01			YN501-YR320,
0148		20		CQ		3-0	34-61-11	SM00041		W		D05925P	A01			YD158-YN260,
0148		20		CQ		3-6	34-61-11	SM00041		W		D05925P	A01			YR321-YR328
0148		20		CQ		3-6	34-61-11	D05925P	A01			SM00041		W		YC051-YC058
0149		22		PA		2-1	34-21-11	D45245P	B05			SM00036		W		YC059-YD157
0149		22		PA		2-7	34-21-11	D45245P	B05			SM00036		W		YD158-YR328
0150		22		PA		6-9	34-21-11	D45245P	B04			D03687B	K15			YC051-YC058
0150		22		PA		7-0	34-21-11	D45245P	B04			D03687B	K15			YC059-YR328
0151		22		PA		0-7	34-21-11	D03687B	A06			D03687B	A07			ALL
0152		22		PA		1-8	34-21-11	D45225P	A01			SM00034		W		YC051-YC058
0152		22		PA		2-2	34-21-11	D45225P	A01			SM00034		W		YC059-YR328
0153		22		PA		1-8	34-21-11	D45225P	A02			SM00035		W		YC051-YC058
0153		22		PA		2-2	34-21-11	D45225P	A02			SM00035		W		YC059-YR328
0154		22		PA		1-8	34-21-11	D45225P	A03			SM00036		W		YC051-YC058
0154		22		PA		2-2	34-21-11	D45225P	A03			SM00036		W		YC059-YR328
0155		22		PA		4-9	34-21-11	D03687B	E10			SM00034		W		YC051-YC058
0155		22		PA		5-0	34-21-11	D03687B	E10			SM00034		W		YC059-YR328
0156		22		PA		4-9	34-21-11	D03687B	E12			SM00035		W		YC051-YC058
0156		22		PA		5-0	34-21-11	D03687B	E12			SM00035		W		YC059-YR328
0157		22		PA		4-9	34-21-11	D03687B	E11			SM00036		W		YC051-YC058
0157		22		PA		5-0	34-21-11	D03687B	E11			SM00036		W		YC059-YR328
0158		22		PA		1-10	34-21-11	D45235P	A20			SM00034		W		YC051-YC058

WIRE LIST

D280A108

91-21-11

Section W0520

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To							
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521	286A0521			E5-2 SHELF WIRE BUNDLE #1 (continued)											
0158	22		PA		2-4	34-21-11	D45235P	A20			SM00034		W		YC059-YR328
0159	22		PA		1-10	34-21-11	D45235P	B01			SM00035		W		YC051-YC058
0159	22		PA		2-4	34-21-11	D45235P	B01			SM00035		W		YC059-YR328
0160	22		PA		1-10	34-21-11	D45225P	A04			D45235P	B02			YC051-YC058
0160	22		PA		2-4	34-21-11	D45225P	A04			D45235P	B02			YC059-YR328
0161	22		PA		0-7	34-21-11	D03687A	G01			D03687A	E02			YC051-YL999, YR301-YR328
0161	22		PA		0-7	34-21-11	D03687A	F01			D03687A	E02			YN231-YN501
0162	22		PA		1-9	34-21-11	D03687A	G08			GD05221	DC..	E	*1	ALL
0163	22		PA		1-9	34-21-11	D03687A	F09			GD05221	DC..	E	*1	ALL
0164	22		PA		1-9	34-21-11	D03687A	G10			GD05221	DC..	E	*4	ALL
0165	22		PA		2-3	34-21-11	D03687A	K03			SM00048		W		ALL
0166	22		PA		2-2	34-21-11	D03687B	E09			SM00048		W		ALL
0167	22		PA		4-4	34-21-11	D45235P	A11			SM00048		W		YC051-YC058
0167	22		PA		4-7	34-21-11	D45235P	A11			SM00048		W		YC059-YR328
0168	24		PK		6-6	34-21-11	D03687B	C05			D45235P	A12			YC051-YC058
0168	24		PK		6-9	34-21-11	D03687B	C05			D45235P	A12			YC059-YR328
0169	24		PK		6-6	34-21-11	D03687B	C06			D45235P	A13			YC051-YC058
0169	24		PK		6-9	34-21-11	D03687B	C06			D45235P	A13			YC059-YR328
0170	24		PK		4-9	34-21-11	D03687B	D01			SM00047		W		YC051-YC058
0170	24		PK		5-0	34-21-11	D03687B	D01			SM00047		W		YC059-YR328
0171	24		PK		1-10	34-21-11	D45235P	A14			SM00047		W		YC051-YC058
0171	24		PK		2-4	34-21-11	D45235P	A14			SM00047		W		YC059-YR328
0172	24		PK		1-10	34-21-11	SM00051		W		D45235P	A15			YC051-YC058
0172	24		PK		2-4	34-21-11	SM00051		W		D45235P	A15			YC059-YR328
0173	22		PA		6-6	34-21-11	D03687B	D03			D45235P	A16			YC051-YC058
0173	22		PA		6-9	34-21-11	D03687B	D03			D45235P	A16			YC059-YR328
0174	22		PA		1-8	34-21-11	D03687B	A03			GD05221	DC..	E	*2	ALL
0175	22		PA		1-8	34-21-11	D03687B	E07			GD05221	DC..	E	*2	ALL
0176	22		PA		1-8	34-21-11	D03687B	K09			GD05221	DC..	E	*3	YC051-YD153
0176	22		PA		1-8	34-21-11	D03687B	K09			GD05221	DC..	E	*2	YD154-YR328
0177	22		PA		1-8	34-21-11	D03687B	K03			GD05221	DC..	E	*3	YC051-YD153
0177	22		PA		1-8	34-21-11	D03687B	K03			GD05221	DC..	=	*3	YD154-YR328
0178	22		PA		6-6	34-21-11	D03687B	F01			D45235P	A17			YC051-YC058
0178	22		PA		6-9	34-21-11	D03687B	F01			D45235P	A17			YC059-YR328
0179	22		PA		6-6	34-21-11	D03687B	F02			D45235P	A18			YC051-YC058
0179	22		PA		6-9	34-21-11	D03687B	F02			D45235P	A18			YC059-YR328
0180	22		PA		6-6	34-21-11	D03687B	E13			D45235P	A19			YC051-YC058
0180	22		PA		6-9	34-21-11	D03687B	E13			D45235P	A19			YC059-YR328

WIRE LIST

D280A108

91-21-11

Section W0520

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521		286A0521					E5-2 SHELF WIRE BUNDLE #1 (continued)									
0182		16		CQ		7-4	34-21-11	D03687C		7		D45209P		F		YC051-YC058
0182		16		CQ		7-7	34-21-11	D03687C		7		D45209P		F		YC059-YR328
0184		22		PA		6-7	34-21-12	D03687A		J03		D45235P		B03		YC051-YC058
0184		22		PA		6-10	34-21-12	D03687A		J03		D45235P		B03		YC059-YR328
0185		22		PA		6-7	34-21-12	D03687A		J04		D45235P		B04		YC051-YC058
0185		22		PA		6-10	34-21-12	D03687A		J04		D45235P		B04		YC059-YR328
0186		22		PA		2-3	34-21-12	D03687A		F04		SM00050			W	ALL
0187		22		PA		4-4	34-21-12	D45235P		B05		SM00050			W	YC051-YC058
0187		22		PA		4-7	34-21-12	D45235P		B05		SM00050			W	YC059-YR328
0188		22		PA		1-9	34-21-12	D45239P		B01		SM00049			W	YC051-YC058
0188		22		PA		2-3	34-21-12	D45239P		B01		SM00049			W	YC059-YR328
0190		22		PA		1-11	34-21-16	D41561P		B17		D45225P		A05		YC051-YC058
0190		22		PA		2-5	34-21-16	D41561P		B17		D45225P		A05		YC059-YR328
0193		22		PA		2-5	34-61-12	D03425		M-		GD05209		DC..	E	YC051-YC058
0193		22		PA		2-8	34-61-12	D03425		M-		GD05209		DC..	E	*3 YC059-YR328
0194		22		PA		6-7	34-61-12	D03425		P-		D45235P		A04		YC051-YC058
0194		22		PA		7-1	34-61-12	D03425		P-		D45235P		A04		YC059-YR328
0195		22		PA		2-4	34-61-12	D03423		G		GD05209		DC..	E	*2 YC051-YC058
0195		22		PA		2-7	34-61-12	D03423		G		GD05209		DC..	E	*2 YC059-YR328
0196		22		PA		7-6	34-61-12	D03423		E		D45221P		B09		YC051-YC058
0196		22		PA		8-0	34-61-12	D03423		E		D45221P		B09		YC059-YR328
0197		22		PA		6-9	34-61-12	D03427		T-		D45235P		A05		YC051-YC058
0197		22		PA		7-3	34-61-12	D03427		T-		D45235P		A05		YC059-YR328
0198		22		PA		2-5	34-61-12	D03425		E		GD05209		DC..	E	*2 YC051-YC058
0198		22		PA		2-8	34-61-12	D03425		E		GD05209		DC..	E	*2 YC059-YR328
0199		22		PA		7-9	34-61-12	D03427		G		D45221P		B12		YC051-YC058
0199		22		PA		8-3	34-61-12	D03427		G		D45221P		B12		YC059-YR328
0200		22		PA		1-3	34-61-12	D03261B		G12		SM00055			W	ALL
0201		22		PA		1-3	34-61-12	D03261B		E12		SM00056			W	ALL
0202		22		PA		1-11	34-61-12	D02179B		G12		SM00055			W	ALL
0203		22		PA		1-11	34-61-12	D02179B		E12		SM00056			W	ALL
0204		20		PA		2-8	34-61-22	D45261P		A14		D06063J		7		YC051-YC058
0204		20		PA		3-2	34-61-22	D45261P		A14		D06063J		7		YC059-YR328
0205		22		PA		6-10	34-16-11	D03687A		F05		D45255P		A07		YC051-YC058
0205		22		PA		7-1	34-16-11	D03687A		F05		D45255P		A07		YC059-YR328
0206		22		PA		6-7	34-16-11	D03687A		C09		D45235P		B13		YC051-YC058
0206		22		PA		6-10	34-16-11	D03687A		C09		D45235P		B13		YC059-YR328
0208		22		PA		1-11	34-21-16	D41561P		B18		SM00047			W	YC051-YC058
0208		22		PA		2-5	34-21-16	D41561P		B18		SM00047			W	YC059-YR328

WIRE LIST

D280A108

91-21-11

Section W0520

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W0521	286A0521				E5-2 SHELF WIRE BUNDLE #1 (continued)											
0209	24	PK			2-3	31-62-15	D45235P	B15			D45245P	B16			YC051-YC058	
0209	24	PK			2-9	31-62-15	D45235P	B15			D45245P	B16			YC059-YR328	
0210	24	PK			2-3	31-62-15	D45235P	B06			D45245P	B12			YC051-YC058	
0210	24	PK			2-9	31-62-15	D45235P	B06			D45245P	B12			YC059-YR328	
0211	24	PK			2-3	31-62-15	D45235P	B07			D45245P	B11			YC051-YC058	
0211	24	PK			2-9	31-62-15	D45235P	B07			D45245P	B11			YC059-YR328	
0212	24	PK			2-3	31-62-15	D45235P	B08			D45245P	B10			YC051-YC058	
0212	24	PK			2-9	31-62-15	D45235P	B08			D45245P	B10			YC059-YR328	
0213	22	PA			2-3	23-43-11	D45245P	B07			D45235P	B12			YC051-YC058	
0213	22	PA			2-9	23-43-11	D45245P	B07			D45235P	B12			YC059-YR328	
0214	22	PA			2-3	SPARE	D45245P	B08			D45235P	B11			YC051-YC058	
0214	22	PA			2-9	SPARE	D45245P	B08			D45235P	B11			YC059-YD157	
0214	22	PA			2-9	23-42-11	D45245P	B08			D45235P	B11			YD158-YR328	
0216	22	G5			2-2	22-13-11	D45235P	B19			D45255P	A16			YC051-YC058	
0216	22	G5			2-8	22-13-11	D45235P	B19			D45255P	A16			YC059-YR328	
0218	24	PK			1-11	31-35-01	D45225P	A13			D45261P	A04			YC051-YC058	
0218	24	PK			2-5	31-35-01	D45225P	A13			D45261P	A04			YC059-YR328	
0219	24	PK			1-11	31-35-01	D45225P	A14			D45261P	A05			YC051-YC058	
0219	24	PK			2-5	31-35-01	D45225P	A14			D45261P	A05			YC059-YR328	
0220	24	PK			1-11	31-35-01	D45225P	A15			D45261P	A06			YC051-YC058	
0220	24	PK			2-5	31-35-01	D45225P	A15			D45261P	A06			YC059-YR328	
0221	22	G5			2-3	22-18-11	D45235P	B16			D45245P	B03			YC051-YC058	
0221	22	G5			2-9	22-18-11	D45235P	B16			D45245P	B03			YC059-YR328	
0223	24	PK			2-0	34-61-17	D02179A	K01			SM00038		W		ALL	
0224	24	PK			4-8	34-61-17	D45245P	A20			SM00038		W		YC051-YC058	
0224	24	PK			4-11	34-61-17	D45245P	A20			SM00038		W		YC059-YR328	
0225	24	PK			1-10	73-21-31	D45265P	A01			SM00003		W		YC051-YC058	
0225	24	PK			2-5	73-21-31	D45265P	A01			SM00003		W		YC059-YR328	
0226	24	PK			1-10	73-21-31	D45265P	A02			SM00004		W		YC051-YC058	
0226	24	PK			2-5	73-21-31	D45265P	A02			SM00004		W		YC059-YR328	
0227	24	PK			1-10	73-21-31	D45265P	A03			SM00010		W		YC051-YC058	
0227	24	PK			2-5	73-21-31	D45265P	A03			SM00010		W		YC059-YR328	
0228	24	PK			1-10	73-21-31	D45265P	A04			SM00006		W		YC051-YC058	
0228	24	PK			2-5	73-21-31	D45265P	A04			SM00006		W		YC059-YR328	
0229	24	PK			1-10	73-21-31	D45265P	A05			SM00008		W		YC051-YC058	
0229	24	PK			2-5	73-21-31	D45265P	A05			SM00008		W		YC059-YR328	
0230	24	G6			2-8	73-21-31	D45247P	B01			SM00005		W		YC051-YC058	
0230	24	G6			3-3	73-21-31	D45247P	B01			SM00005		W		YC059-YR328	
0231	24	G6			2-8	73-21-31	D45247P	B02			SM00009		W		YC051-YC058	

WIRE LIST

D280A108

91-21-11

Section W0520

Page 12

Nov 12/2012



WIRE LIST

91-21-11

Section W0520

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W0521	286A0521				E5-2 SHELF WIRE BUNDLE #1 (continued)											
0263	22	PA			5-5	34-61-19	D45221P	B14			SM00096		W		YC053-YC058	
0263	22	PA			6-2	34-61-19	D45221P	B14			SM00096		W		YC059-YR328	
0264	22	PA			5-5	34-61-19	D45221P	B15			SM00097		W		YC053-YC058	
0264	22	PA			6-2	34-61-19	D45221P	B15			SM00097		W		YC059-YR328	
0265	22	PA			6-11	34-21-12	D03687A	F03			D45261P	B19			YL951-YR328	
0266	22	G5			5-1	34-21-22	D03693A	F03			D45261P	B20			YL951-YR328	
0277	24	PK			1-11	34-61-26	D05925P	A05			D45293P	A08			YC059-YR328	
0278	24	PK			6-3	34-61-26	D05925P	B07			TB0524Y	A015	1A		YC059-YR328	
0279	22	PA			2-2	34-61-18	D02179A	K08			GD05209	DC..	E		YC059-YR328	
0280	24	PK			8-2	22-11-53	D45293P	A05			D41251J	21			YC059-YR328	
0281	24	PK			8-2	22-11-53	D45293P	A06			D41251J	22			YC059-YR328	
0282	24	PK			8-2	22-11-53	D45293P	A07			D41251J	23			YC059-YR328	
0283	24	PK			4-10	22-11-53	D45293P	B03			TB0522Y	B007	1A		YC059-YR328	
0284	24	PK			4-2	22-11-53	D41251J	24			TB0522Y	B007	1A		YC059-YR328	
0295	20	PA			3-3	23-32-21	D45211P	B01			D45367P	A15			YL951-YL967, YN231-YN235	
0296	22	PA			4-9	34-61-19	D02179A	J14			SM00062		W		YL951-YR328	
0297	22	PA			4-9	34-61-19	D02179A	J15			SM00063		W		YL951-YR328	
0298	22	PA			4-2	34-61-19	D03261A	J14			SM00062		W		YL951-YR328	
0299	22	PA			4-2	34-61-19	D03261A	J15			SM00063		W		YL951-YR328	
0300	22	PA			3-4	34-61-19	D45221P	B16			SM00062		W		YL951-YR328	
0301	22	PA			3-4	34-61-19	D45221P	B17			SM00063		W		YL951-YR328	
0400	22	PA			3-10	23-32-21	D45209P	A10			D45367P	A09			YL951-YL967, YN231-YN235	
0401	22	PA			3-10	23-32-21	D45209P	B10			D45367P	B09			YL951-YL967, YN231-YN235	
2011B	22	PB	EK		1-11	27-32-11	D45239P	B05			D45261P	B13			YC051-YC058	
2011B	22	PB	EK		2-5	27-32-11	D45239P	B05			D45261P	B13			YC059-YR328	
2011R	22	PB	EK		0-0	27-32-11	D45239P	B04			D45261P	B12			ALL	
2501B	24	Y2	AA		6-0	34-61-22	D45255P	B10			TB0523Y	B005	1A		YC051-YC058	
2501B	24	Y2	AA		6-3	34-61-22	D45255P	B10			TB0523Y	B005	1A		YC059-YR328	
2501R	24	Y2	AA		0-0	34-61-22	D45255P	B09			TB0523Y	A005	1A		ALL	
2501Z			AA		0-0	34-61-22	D45255P	PERG	1F		GB00523	ST..	1A		ALL	
2502B	24	Y2	AB		3-2	34-61-11	TB0521Y	B003	1A		D03263	M			YC051-YC058	
2502B	24	Y2	AB		3-5	34-61-11	TB0521Y	B003	1A		D03263	M			YC059-YR328	
2502R	24	Y2	AB		0-0	34-61-11	TB0521Y	A003	1A		D03263	L			ALL	
2502Z			AB		0-0	34-61-11	GB00521	ST..	1A		D03263	DED			ALL	
2503B	24	Y2	AC		3-7	34-61-11	D02179A	E13			D03267	M			YC051-YC058	
2503B	24	Y2	AC		3-10	34-61-11	D02179A	E13			D03267	M			YC059-YR328	

WIRE LIST

D280A108

91-21-11

Section W0520

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521		286A0521					E5-2 SHELF WIRE BUNDLE #1 (continued)									
2503R		24		Y2	AC	0-0	34-61-11	D02179A	D13			D03267	L			ALL
2503Z					AC	0-0	34-61-11	GB00523	ST..	1A		D03267	DED			ALL
2504B		24		Y2	AD	3-7	34-61-11	D02179A	H13			D03267	P			YC051-YC058
2504B		24		Y2	AD	3-10	34-61-11	D02179A	H13			D03267	P			YC059-YR328
2504R		24		Y2	AD	0-0	34-61-11	D02179A	G13			D03267	N			ALL
2504Z					AD	0-0	34-61-11	GB00524	ST..	1A		D03267	DED			ALL
2505B		24		Y2	AE	2-1	34-61-14	D03687B	A09			TB0523Y	B007	1A		ALL
2505R		24		Y2	AE	0-0	34-61-14	D03687B	A08			TB0523Y	A007	1A		ALL
2505Z					AE	0-0	34-61-14	D03687B	PERG	1A		GB00523	ST..	1A		ALL
2506B		24		M5	AF	0-25	34-61-12	D02179B	B04			D03261A	B14			ALL
2506R		24		M5	AF	0-0	34-61-12	D02179B	A04			D03261A	A14			ALL
2506ZI					AF	0-0	34-61-12	GB00523	ST..	1A		GB00521	ST..	1A		ALL
2506ZO					AF	0-0	34-61-12	GB00524	ST..	1A		GB00522	ST..	1A		ALL
2507B		24		M5	AG	0-25	34-61-12	D02179A	B14			D03261B	B04			ALL
2507R		24		M5	AG	0-0	34-61-12	D02179A	A14			D03261B	A04			ALL
2507ZI					AG	0-0	34-61-12	GB00523	ST..	1A		GB00521	ST..	1A		ALL
2507ZO					AG	0-0	34-61-12	GB00524	ST..	1A		GB00522	ST..	1A		ALL
2509B		24		Y2	AI	2-10	34-61-14	D03263	F			TB0523Z	B013	1A		YC051-YC058
2509B		24		Y2	AI	3-1	34-61-14	D03263	F			TB0523Z	B013	1A		YC059-YR328
2509R		24		Y2	AI	0-0	34-61-14	D03263	E			TB0523Z	A013	1A		ALL
2509Z					AI	0-0	34-61-14	D03263	DED			GB00523	ST..	1A		ALL
2510B		24		Y2	AJ	3-0	34-61-14	D03267	U			TB0523Y	B001	1A		YC051-YC058
2510B		24		Y2	AJ	3-3	34-61-14	D03267	U			TB0523Y	B001	1A		YC059-YR328
2510R		24		Y2	AJ	0-0	34-61-14	D03267	T			TB0523Y	A001	1A		ALL
2510Z					AJ	0-0	34-61-14	D03267	DED			GB00523	ST..	1A		ALL
2511B		24		Y2	AK	3-0	34-61-14	D03267	F			TB0523Y	B007	1A		YC051-YC058
2511B		24		Y2	AK	3-3	34-61-14	D03267	F			TB0523Y	B007	1A		YC059-YR328
2511R		24		Y2	AK	0-0	34-61-14	D03267	E			TB0523Y	A007	1A		ALL
2511Z					AK	0-0	34-61-14	D03267	DED			GB00523	ST..	1A		ALL
2512B		24		Y2	AL	2-4	34-61-14	D03425	B			TB0523Y	B007	1A		YC051-YC058
2512B		24		Y2	AL	2-7	34-61-14	D03425	B			TB0523Y	B007	1A		YC059-YR328
2512R		24		Y2	AL	0-0	34-61-14	D03425	A			TB0523Y	A007	1A		ALL
2512Z					AL	0-0	34-61-14	D03425	DED			GB00523	ST..	1A		ALL
2513B		24		Y2	AM	2-3	34-61-14	D03425	D			TB0523Y	B001	1A		YC051-YC058
2513B		24		Y2	AM	2-6	34-61-14	D03425	D			TB0523Y	B001	1A		YC059-YR328
2513R		24		Y2	AM	0-0	34-61-14	D03425	C			TB0523Y	A001	1A		ALL
2513Z					AM	0-0	34-61-14	D03425	DED			GB00523	ST..	1A		ALL
2514B		22		X2	AN	6-10	34-61-18	D45225P	B02			D03263	K			YC051-YC058
2514B		22		X2	AN	2-5	31-32-15	D45225P	B02			SM00112		W		YC059-YR328

WIRE LIST

D280A108

91-21-11

Section W0520

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521	286A0521			E5-2 SHELF WIRE BUNDLE #1 (continued)											
2514R	22	X2	AN		0-0	34-61-18	D45225P	B01			D03263	J			YC051-YC058
2514R	22	X2	AN		0-0	31-32-15	D45225P	B01			SM00111		W		YC059-YR328
2514Z			AN		0-0	34-61-18	D45225P	PERG	1F		D03263	DED			YC051-YC058
2514Z			AN		0-0	31-32-15	D45225P	PERG	1F		SM00113		W		YC059-YR328
2515B	22	X2	AP		5-1	34-61-18	D45225P	B04			TB0522Y	B021	1A		YC051-YC058
2515B	22	X2	AP		2-8	31-32-15	D41561P	B10			SM00112		W		YC059-YR328
2515R	22	X2	AP		0-0	34-61-18	D45225P	B03			TB0522Y	A021	1A		YC051-YC058
2515R	22	X2	AP		0-0	31-32-15	D41561P	B09			SM00111		W		YC059-YR328
2515Z			AP		0-0	34-61-18	D45225P	PERG	1F		GB00522	ST..	1A		YC051-YC058
2515Z			AP		0-0	31-32-15	D41561P	PERG	1F		SM00113		W		YC059-YR328
2516B	22	X2	AQ		2-0	34-61-18	D45255P	A18			SM00070		W		YC051-YC058
2516B	22	X2	AQ		2-6	31-32-15	D45255P	A18			SM00070		W		YC059-YR328
2516R	22	X2	AQ		0-0	34-61-18	D45255P	A17			SM00069		W		YC051-YC058
2516R	22	X2	AQ		0-0	31-32-15	D45255P	A17			SM00069		W		YC059-YR328
2516Z			AQ		0-0	34-61-18	D45255P	PERG	1F		SM00077		W		YC051-YC058
2516Z			AQ		0-0	31-32-15	D45255P	PERG	1F		SM00077		W		YC059-YR328
2517B	24	Y2	AR		2-3	34-61-22	D03261A	B09			TB0523Y	B005	1A		ALL
2517R	24	Y2	AR		0-0	34-61-22	D03261A	A09			TB0523Y	A005	1A		ALL
2517Z			AR		0-0	34-61-22	D03261A	DED			GB00523	ST..	1A		ALL
2518B	24	Y2	AS		6-2	34-61-14	D45255P	B16			TB0523Z	B013	1A		YC051-YC058
2518B	24	Y2	AS		6-5	34-61-14	D45255P	B16			TB0523Z	B013	1A		YC059-YR328
2518R	24	Y2	AS		0-0	34-61-14	D45255P	B15			TB0523Z	A013	1A		ALL
2518Z			AS		0-0	34-61-14	D45255P	PERG	1F		GB00523	ST..	1A		ALL
2519B	24	Y2	AT		3-7	34-61-14	D41251J	2			TB0523Z	B013	1A		YC051-YC058
2519B	24	Y2	AT		3-10	34-61-14	D41251J	2			TB0523Z	B013	1A		YC059-YR328
2519R	24	Y2	AT		0-0	34-61-14	D41251J	1			TB0523Z	A013	1A		ALL
2519Z			AT		0-0	34-61-14	D41251J	S/R			GB00523	ST..	1A		ALL
2520B	22	X2	AU		5-4	34-61-14	D45239P	B10			TB0523Z	B013	1A		YC051-YC058
2520B	22	X2	AU		6-1	34-61-14	D45239P	B10			TB0523Z	B013	1A		YC059-YR328
2520R	22	X2	AU		0-0	34-61-14	D45239P	B09			TB0523Z	A013	1A		ALL
2520Z			AU		0-0	34-61-14	D45239P	PERG	1F		GB00523	ST..	1A		ALL
2521B	24	Y2	AV		6-2	34-61-14	D45255P	B18			TB0523Z	B013	1A		YC051-YC058
2521B	24	Y2	AV		6-5	34-61-14	D45255P	B18			TB0523Z	B013	1A		YC059-YR328
2521R	24	Y2	AV		0-0	34-61-14	D45255P	B17			TB0523Z	A013	1A		ALL
2521Z			AV		0-0	34-61-14	D45255P	PERG	1F		GB00523	ST..	1A		ALL
2522B	24	Y2	AW		6-0	34-61-14	D45261P	B08			TB0523Z	B013	1A		YC051-YC058
2522B	24	Y2	AW		6-3	34-61-14	D45261P	B08			TB0523Z	B013	1A		YC059-YR328
2522R	24	Y2	AW		0-0	34-61-14	D45261P	A08			TB0523Z	A013	1A		ALL
2522Z			AW		0-0	34-61-14	D45261P	PERG	1F		GB00523	ST..	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0520

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521		286A0521			E5-2 SHELF WIRE BUNDLE #1 (continued)											
2523B		22		X2	AX	5-5	34-61-15	D45261P	B07			TB0523Y	B009	1A		YC051-YC058
2523B		22		X2	AX	6-2	34-61-15	D45261P	B07			TB0523Y	B009	1A		YC059-YR328
2523R		22		X2	AX	0-0	34-61-15	D45261P	A07			TB0523Y	A009	1A		ALL
2523Z					AX	0-0	34-61-15	D45261P	PERG	1F		GB00523	ST..	1A		ALL
2524B		22		X2	AY	2-10	34-61-15	D03263	S			TB0523Y	B009	1A		YC051-YC058
2524B		22		X2	AY	3-1	34-61-15	D03263	S			TB0523Y	B009	1A		YC059-YR328
2524R		22		X2	AY	0-0	34-61-15	D03263	R			TB0523Y	A009	1A		ALL
2524Z					AY	0-0	34-61-15	D03263	DED			GB00523	ST..	1A		ALL
2525B		22		X2	AZ	6-2	34-61-15	D45245P	A02			TB0523Y	B009	1A		YC051-YC058
2525B		22		X2	AZ	6-5	34-61-15	D45245P	A02			TB0523Y	B009	1A		YC059-YR328
2525R		22		X2	AZ	0-0	34-61-15	D45245P	A01			TB0523Y	A009	1A		ALL
2525Z					AZ	0-0	34-61-15	D45245P	PERG	1F		GB00523	ST..	1A		ALL
2526B		22		X2	BA	3-1	34-61-15	D03267	S			TB0523Y	B011	1A		YC051-YC058
2526B		22		X2	BA	3-4	34-61-15	D03267	S			TB0523Y	B011	1A		YC059-YR328
2526R		22		X2	BA	0-0	34-61-15	D03267	R			TB0523Y	A011	1A		ALL
2526Z					BA	0-0	34-61-15	D03267	DED			GB00523	ST..	1A		ALL
2527B		22		X2	BB	3-7	34-61-18	D02179A	H11			D03267	K			YC051-YC058
2527B		24		Y2	BB	6-3	34-61-18	D02179A	H11			D45293P	B01			YC059-YR328
2527R		22		X2	BB	0-0	34-61-18	D02179A	G11			D03267	J			YC051-YC058
2527R		24		Y2	BB	0-0	34-61-18	D02179A	G11			D45293P	A01			YC059-YR328
2527Z					BB	0-0	34-61-18	GB00524	ST..	1A		D03267	DED			YC051-YC058
2527Z					BB	0-0	34-61-18	GB00524	ST..	1A		D45293P	PERG	1F		YC059-YR328
2528B		24		Y2	BC	2-5	34-61-14	D03693B	A09			TB0523Y	B001	1A		ALL
2528R		24		Y2	BC	0-0	34-61-14	D03693B	A08			TB0523Y	A001	1A		ALL
2528Z					BC	0-0	34-61-14	D03693B	PERG	1A		GB00523	ST..	1A		ALL
2529B		22		N2	BD	6-6	34-61-15	D02179B	H09			D45245P	A06			YC051-YC055
2529B		22		X2	BD	2-3	34-61-15	D02179B	H09			TB0522Y	B011	1A		YC056-YR328
2529R		22		N2	BD	0-0	34-61-15	D02179B	G09			D45245P	A05			YC051-YC055
2529R		22		X2	BD	0-0	34-61-15	D02179B	G09			TB0522Y	A011	1A		YC056-YR328
2529Z					BD	0-0	34-61-15	GB00524	ST..	1A		D45245P	PERG	1F		YC051-YC055
2529Z					BD	0-0	34-61-15	GB00524	ST..	1A		GB00522	ST..	1A		YC056-YR328
2530B		22		X2	BE	6-2	34-61-15	D45245P	A04			TB0523Y	B011	1A		YC051-YC058
2530B		22		X2	BE	6-5	34-61-15	D45245P	A04			TB0523Y	B011	1A		YC059-YR328
2530R		22		X2	BE	0-0	34-61-15	D45245P	A03			TB0523Y	A011	1A		ALL
2530Z					BE	0-0	34-61-15	D45245P	PERG	1F		GB00523	ST..	1A		ALL
2531B		24		Y2	BF	6-11	34-21-12	D03687A	E09			D45245P	B02			YC051-YC058
2531B		24		Y2	BF	7-2	34-21-12	D03687A	E09			D45245P	B02			YC059-YR328
2531R		24		Y2	BF	0-0	34-21-12	D03687A	D09			D45245P	B01			ALL
2531Z					BF	0-0	34-21-12	D03687A	PERG	1A		D45245P	PERG	1F		ALL

WIRE LIST

D280A108

91-21-11

Section W0520

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description		From				To					
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521		286A0521			E5-2 SHELF WIRE BUNDLE #1 (continued)											
2532B		22	X2	BG		6-7	34-21-12	D03687A	J08			D45239P	A07			YC051-YC058
2532B		22	X2	BG		6-10	34-21-12	D03687A	J08			D45239P	A07			YC059-YR328
2532R		22	X2	BG		0-0	34-21-12	D03687A	H08			D45239P	A06			ALL
2532Z				BG		0-0	34-21-12	D03687A	PERG	1A		D45239P	PERG	1F		ALL
2533B		24	Y2	BH		6-3	34-21-13	D45235P	B10			TB0524Z	B017	1A		YC051-YC058
2533B		24	Y2	BH		6-6	34-21-13	D45235P	B10			TB0524Z	B017	1A		YC059-YR328
2533R		24	Y2	BH		0-0	34-21-13	D45235P	B09			TB0524Z	A017	1A		ALL
2533Z				BH		0-0	34-21-13	D45235P	PERG	1F		GB00524	ST..	1A		ALL
2534B		24	Y2	BI		6-3	34-21-13	D45239P	A12			TB0524Z	B017	1A		YC051-YC052
2534R		24	Y2	BI		0-0	34-21-13	D45239P	A11			TB0524Z	A017	1A		YC051-YC052
2534Z				BI		0-0	34-21-13	D45239P	PERG	1F		GB00524	ST..	1A		YC051-YC052
2535B		24	Y2	BJ		2-1	34-21-13	D03687B	C11			TB0524Z	B017	1A		ALL
2535R		24	Y2	BJ		0-0	34-21-13	D03687B	C10			TB0524Z	A017	1A		ALL
2535Z				BJ		0-0	34-21-13	D03687B	PERG	1A		GB00524	ST..	1A		ALL
2536B		24	Y2	BK		6-5	34-21-13	D41561P	B03			TB0524Z	B017	1A		YC051-YC058
2536B		24	Y2	BK		6-8	34-21-13	D41561P	B03			TB0524Z	B017	1A		YC059-YR328
2536R		24	Y2	BK		0-0	34-21-13	D41561P	A03			TB0524Z	A017	1A		ALL
2536Z				BK		0-0	34-21-13	D41561P	PERG	1F		GB00524	ST..	1A		ALL
2537B		24	Y2	BL		6-2	34-21-13	D41561P	B04			TB0524Y	B011	1A		YC051-YC058
2537B		24	Y2	BL		6-5	34-21-13	D41561P	B04			TB0524Y	B011	1A		YC059-YR328
2537R		24	Y2	BL		0-0	34-21-13	D41561P	A04			TB0524Y	A011	1A		ALL
2537Z				BL		0-0	34-21-13	D41561P	PERG	1F		GB00524	ST..	1A		ALL
2538B		24	Y2	BM		1-11	34-21-13	D03687B	E06			TB0524Y	B011	1A		ALL
2538R		24	Y2	BM		0-0	34-21-13	D03687B	E05			TB0524Y	A011	1A		ALL
2538Z				BM		0-0	34-21-13	D03687B	PERG	1A		GB00524	ST..	1A		YC051-YC058, YL951-YR328
2538Z				BM		0-0	34-21-13	D03687B	PERG	1A		TB0524Y	DED			YC059-YD170
2539B		24	Y2	BN		1-11	34-21-13	D03687B	K12			D03687A	E06			ALL
2539R		24	Y2	BN		0-0	34-21-13	D03687B	K11			D03687A	D06			ALL
2539Z				BN		0-0	34-21-13	D03687B	DED			D03687A	DED			ALL
2540B		24	Y2	BP		2-3	34-21-13	D45255P	A09			SM00085		W		YC051-YC058
2540B		24	Y2	BP		2-9	34-21-13	D45255P	A09			SM00085		W		YC059-YD157
2540B		24	Y2	BP		6-9	34-21-13	D45255P	A09			TB0524Z	B017	1A		YD158-YD170
2540B		24	Y2	BP		3-7	34-21-13	D45255P	A09			SM00088		W		YL951-YL954, YN231-YN235
2540B		24	Y2	BP		3-10	34-21-13	D45255P	A09			SM00088		W		YL955-YL999, YN236-YR328
2540R		24	Y2	BP		0-0	34-21-13	D45255P	A08			SM00084		W		YC051-YD157
2540R		24	Y2	BP		0-0	34-21-13	D45255P	A08			TB0524Z	A017	1A		YD158-YD170

WIRE LIST

D280A108

91-21-11
Section W0520
Page 18
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521		286A0521					E5-2 SHELF WIRE BUNDLE #1 (continued)									
2540R		24		Y2	BP	0-0	34-21-13	D45255P	A08			SM00087		W		YL951-YR328
2540Z					BP	0-0	34-21-13	D45255P	PERG	1F		SM00086		W		YC051-YD157
2540Z					BP	0-0	34-21-13	D45255P	PERG	1F		GB00524	ST..	1A		YD158-YD170
2540Z					BP	0-0	34-21-13	D45255P	PERG	1F		SM00090		W		YL951-YR328
2541B		24		Y2	BQ	5-5	34-21-13	D45255P	A11			TB0523Y	B003	1A		YC051-YC058
2541B		24		Y2	BQ	6-2	34-21-13	D45255P	A11			TB0523Y	B003	1A		YC059-YD170
2541B		24		Y2	BQ	5-3	34-21-13	D45255P	A11			SM00043		W		YL951-YR328
2541R		24		Y2	BQ	0-0	34-21-13	D45255P	A10			TB0523Y	A003	1A		YC051-YD170
2541R		24		Y2	BQ	0-0	34-21-13	D45255P	A10			SM00042		W		YL951-YR328
2541Z					BQ	0-0	34-21-13	D45255P	PERG	1F		GB00524	ST..	1A		YC051-YC064
2541Z					BQ	0-0	34-21-13	D45255P	PERG	1F		TB0523Y	DED			YC065-YD170
2541Z					BQ	0-0	34-21-13	D45255P	PERG	1F		SM00044		W		YL951-YR328
2542B		24		Y2	BR	2-0	34-21-13	D03687B	G08			TB0523Y	B003	1A		YC051-YD170
2542B		24		Y2	BR	1-9	34-21-13	D03687B	G08			SM00043		W		YL951-YR328
2542R		24		Y2	BR	0-0	34-21-13	D03687B	G07			TB0523Y	A003	1A		YC051-YD170
2542R		24		Y2	BR	0-0	34-21-13	D03687B	G07			SM00042		W		YL951-YR328
2542Z					BR	0-0	34-21-13	D03687B	PERG	1A		GB00524	ST..	1A		YC051-YC058
2542Z					BR	0-0	34-21-13	D03687B	PERG	1A		TB0523Y	DED			YC059-YD170
2542Z					BR	0-0	34-21-13	D03687B	PERG	1A		SM00044		W		YL951-YR328
2543B		24		Y2	BS	3-5	34-21-13	D41251J	14			TB0523Y	B003	1A		YC051-YC058
2543B		24		Y2	BS	3-8	34-21-13	D41251J	14			TB0523Y	B003	1A		YC059-YD170
2543B		24		Y2	BS	3-5	34-21-13	D41251J	14			SM00043		W		YL951-YR328
2543R		24		Y2	BS	0-0	34-21-13	D41251J	13			TB0523Y	A003	1A		YC051-YD170
2543R		24		Y2	BS	0-0	34-21-13	D41251J	13			SM00042		W		YL951-YR328
2543Z					BS	0-0	34-21-13	D41251J	S/R			GB00524	ST..	1A		YC051-YC064
2543Z					BS	0-0	34-21-13	D41251J	S/R			GB00523	ST..	1A		YC065-YD170
2543Z					BS	0-0	34-21-13	D41251J	S/R			SM00044		W		YL951-YR328
2544B		24		Y2	BT	2-1	34-21-13	D02179A	B03			TB0524Z	B017	1A		ALL
2544R		24		Y2	BT	0-0	34-21-13	D02179A	A03			TB0524Z	A017	1A		ALL
2544Z					BT	0-0	34-21-13	D02179A	DED			GB00524	ST..	1A		ALL
2545B		24		Y2	BU	2-9	34-21-13	D03261A	B03			TB0524Z	B017	1A		ALL
2545R		24		Y2	BU	0-0	34-21-13	D03261A	A03			TB0524Z	A017	1A		ALL
2545Z					BU	0-0	34-21-13	D03261A	DED			GB00524	ST..	1A		ALL
2546B		24		Y2	BV	6-6	34-21-13	D45255P	A13			TB0524Z	B017	1A		YC051-YC058
2546B		24		Y2	BV	6-9	34-21-13	D45255P	A13			TB0524Z	B017	1A		YC059-YR328
2546R		24		Y2	BV	0-0	34-21-13	D45255P	A12			TB0524Z	A017	1A		ALL
2546Z					BV	0-0	34-21-13	D45255P	PERG	1F		GB00524	ST..	1A		ALL
2547B		24		Y2	BW	6-4	34-21-13	D45255P	A15			TB0524Y	B011	1A		YC051-YC058
2547B		24		Y2	BW	6-7	34-21-13	D45255P	A15			TB0524Y	B011	1A		YC059-YR328

WIRE LIST

D280A108

91-21-11

Section W0520

Page 19

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521	286A0521			E5-2 SHELF WIRE BUNDLE #1 (continued)											
2547R	24	Y2	BW		0-0	34-21-13	D45255P	A14			TB0524Y	A011	1A		ALL
2547Z			BW		0-0	34-21-13	D45255P	PERG	1F		GB00524	ST..	1A		ALL
2548B	24	Y2	BX		3-9	34-21-14	D41251J	16			TB0523Z	B017	1A		YC051-YC058
2548B	24	Y2	BX		4-0	34-21-14	D41251J	16			TB0523Z	B017	1A		YC059-YR328
2548R	24	Y2	BX		0-0	34-21-14	D41251J	15			TB0523Z	A017	1A		ALL
2548Z			BX		0-0	34-21-14	D41251J	S/R			GB00523	ST..	1A		ALL
2549B	24	Y2	BY		2-5	34-21-14	D03687B	K05			TB0523Z	B021	1A		ALL
2549R	24	Y2	BY		0-0	34-21-14	D03687B	K04			TB0523Z	A021	1A		ALL
2549Z			BY		0-0	34-21-14	D03687B	PERG	1A		GB00523	ST..	1A		ALL
2550B	24	Y2	BZ		6-4	34-21-14	D45255P	A02			TB0523Z	B021	1A		YC051-YC058
2550B	24	Y2	BZ		6-7	34-21-14	D45255P	A02			TB0523Z	B021	1A		YC059-YR328
2550R	24	Y2	BZ		0-0	34-21-14	D45255P	A01			TB0523Z	A021	1A		ALL
2550Z			BZ		0-0	34-21-14	D45255P	PERG	1F		GB00523	ST..	1A		ALL
2551B	24	Y2	CA		2-6	34-21-14	D03687A	B09			TB0523Z	B021	1A		ALL
2551R	24	Y2	CA		0-0	34-21-14	D03687A	A09			TB0523Z	A021	1A		ALL
2551Z			CA		0-0	34-21-14	D03687A	PERG	1A		GB00523	ST..	1A		ALL
2552B	24	Y2	CB		6-10	34-21-14	D45255P	A04			D03687A	B03			YC051-YC058
2552B	24	Y2	CB		7-1	34-21-14	D45255P	A04			D03687A	B03			YC059-YR328
2552R	24	Y2	CB		0-0	34-21-14	D45255P	A03			D03687A	A03			ALL
2552Z			CB		0-0	34-21-14	D45255P	PERG	1F		D03687A	PERG	1A		ALL
2553B	24	Y2	CC		6-10	34-21-14	D45255P	A06			D03687A	B07			YC051-YC058
2553B	24	Y2	CC		7-1	34-21-14	D45255P	A06			D03687A	B07			YC059-YD155
2553R	24	Y2	CC		0-0	34-21-14	D45255P	A05			D03687A	A07			YC051-YD155
2553Z			CC		0-0	34-21-14	D45255P	PERG	1F		D03687A	PERG	1A		YC051-YD155
2554B	24	Y2	CD		6-3	34-21-14	D45265P	A07			TB0523Z	B021	1A		YC051-YC058
2554B	24	Y2	CD		6-6	34-21-14	D45265P	A07			TB0523Z	B021	1A		YC059-YR328
2554R	24	Y2	CD		0-0	34-21-14	D45265P	A06			TB0523Z	A021	1A		ALL
2554Z			CD		0-0	34-21-14	D45265P	PERG	1F		GB00523	ST..	1A		ALL
2555B	24	Y2	CE		6-9	34-21-14	D45265P	A09			D03687A	B05			YC051-YC058
2555B	24	Y2	CE		7-0	34-21-14	D45265P	A09			D03687A	B05			YC059-YR328
2555R	24	Y2	CE		0-0	34-21-14	D45265P	A08			D03687A	A05			ALL
2555Z			CE		0-0	34-21-14	D45265P	PERG	1F		D03687A	PERG	1A		ALL
2556B	24	Y2	CF		6-2	34-21-14	D41561P	B11			TB0523Z	B017	1A		YC051-YC058
2556B	24	Y2	CF		6-5	34-21-14	D41561P	B11			TB0523Z	B017	1A		YC059-YD157
2556B	24	Y2	CF		7-3	34-21-14	D45209P	B08			TB0523Z	B017	1A		YD158-YR328
2556R	24	Y2	CF		0-0	34-21-14	D41561P	A11			TB0523Z	A017	1A		YC051-YD157
2556R	24	Y2	CF		0-0	34-21-14	D45209P	B07			TB0523Z	A017	1A		YD158-YR328
2556Z			CF		0-0	34-21-14	D41561P	PERG	1F		GB00523	ST..	1A		YC051-YD157
2556Z			CF		0-0	34-21-14	D45209P	PERG	1F		GB00523	ST..	1A		YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W0520

Page 20

Nov 12/2012

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521		286A0521					E5-2 SHELF WIRE BUNDLE #1 (continued)									
2557B		24		Y2	CG	6-2	34-21-14	D41561P	B07			TB0523Z	B017	1A		YC051-YC058
2557B		24		Y2	CG	6-5	34-21-14	D41561P	B07			TB0523Z	B017	1A		YC059-YR328
2557R		24		Y2	CG	0-0	34-21-14	D41561P	A07			TB0523Z	A017	1A		ALL
2557Z					CG	0-0	34-21-14	D41561P	PERG	1F		GB00523	ST..	1A		ALL
2558B		24		Y2	CH	2-1	34-21-14	D02179A	E07			TB0523Z	B017	1A		ALL
2558R		24		Y2	CH	0-0	34-21-14	D02179A	D07			TB0523Z	A017	1A		ALL
2558Z					CH	0-0	34-21-14	D02179A	DED			GB00523	ST..	1A		ALL
2559B		24		Y2	CI	2-6	34-21-14	D03261A	E07			TB0523Z	B017	1A		ALL
2559R		24		Y2	CI	0-0	34-21-14	D03261A	D07			TB0523Z	A017	1A		ALL
2559Z					CI	0-0	34-21-14	D03261A	DED			GB00523	ST..	1A		ALL
2565B		22		X2	CP	2-7	34-61-18	D02179A	E09			TB0522Y	B021	1A		YC051-YC058
2565B		24		Y2	CP	4-9	34-61-18	D02179A	E09			SM00070		W		YC059-YR328
2565R		22		X2	CP	0-0	34-61-18	D02179A	D09			TB0522Y	A021	1A		YC051-YC058
2565R		24		Y2	CP	0-0	34-61-18	D02179A	D09			SM00069		W		YC059-YR328
2565Z					CP	0-0	34-61-18	D02179A	DED			GB00522	ST..	1A		YC051-YC058
2565Z					CP	0-0	34-61-18	D02179A	DED			SM00077		W		YC059-YR328
2566B		24		Y2	CQ	5-3	22-11-51	D03261A	H07			D41561P	B05			YC051-YC058
2566B		24		Y2	CQ	6-0	22-11-51	D03261A	H07			D41561P	B05			YC059-YR328
2566R		24		Y2	CQ	0-0	22-11-51	D03261A	G07			D41561P	A05			ALL
2566Z					CQ	0-0	22-11-51	GB00522	ST..	1A		D41561P	PERG	1F		ALL
2567B		24		Y2	CR	6-5	22-11-51	D02179A	H07			D41561P	B06			YC051-YC058
2567B		24		Y2	CR	6-8	22-11-51	D02179A	H07			D41561P	B06			YC059-YR328
2567R		24		Y2	CR	0-0	22-11-51	D02179A	G07			D41561P	A06			ALL
2567Z					CR	0-0	22-11-51	GB00524	ST..	1A		D41561P	PERG	1F		ALL
2569B		22		X2	CT	2-7	28-41-11	D03261A	E05			TB0524Y	B009	1A		ALL
2569R		22		X2	CT	0-0	28-41-11	D03261A	D05			TB0524Y	A009	1A		ALL
2569Z					CT	0-0	28-41-11	GB00522	ST..	1A		GB00524	ST..	1A		ALL
2570B		22		X2	CU	1-11	28-41-11	D02179A	E05			TB0524Y	B009	1A		ALL
2570R		22		X2	CU	0-0	28-41-11	D02179A	D05			TB0524Y	A009	1A		ALL
2570Z					CU	0-0	28-41-11	D02179A	DED			GB00524	ST..	1A		ALL
2571B		22		X2	CV	6-1	28-41-11	D45239P	B12			TB0524Y	B009	1A		YC051-YC058
2571B		22		X2	CV	6-4	28-41-11	D45239P	B12			TB0524Y	B009	1A		YC059-YR328
2571R		22		X2	CV	0-0	28-41-11	D45239P	B11			TB0524Y	A009	1A		ALL
2571Z					CV	0-0	28-41-11	D45239P	PERG	1F		GB00524	ST..	1A		ALL
2572B		24		Y2	CW	1-11	31-35-01	D45225P	B06			D45261P	B01			YC051-YC058
2572B		24		Y2	CW	2-5	31-35-01	D45225P	B06			D45261P	B01			YC059-YR328
2572R		24		Y2	CW	0-0	31-35-01	D45225P	B05			D45261P	A01			ALL
2572Z					CW	0-0	31-35-01	D45225P	PERG	1F		D45261P	PERG	1F		ALL
2573B		24		Y2	CX	1-11	31-35-01	D45225P	B08			D45261P	B02			YC051-YC058

WIRE LIST

D280A108

91-21-11

Section W0520

Page 21

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521	286A0521				E5-2 SHELF WIRE BUNDLE #1 (continued)										
2573B	24	Y2	CX		2-5	31-35-01	D45225P	B08			D45261P	B02			YC059-YR328
2573R	24	Y2	CX		0-0	31-35-01	D45225P	B07			D45261P	A02			ALL
2573Z			CX		0-0	31-35-01	D45225P	PERG	1F		D45261P	PERG	1F		ALL
2574B	24	Y2	CY		2-1	31-62-15	D45225P	B10			D45245P	A12			YC051-YC058
2574B	24	Y2	CY		2-7	31-62-15	D45225P	B10			D45245P	A12			YC059-YR328
2574R	24	Y2	CY		0-0	31-62-15	D45225P	B09			D45245P	A11			ALL
2574Z			CY		0-0	31-62-15	D45225P	PERG	1F		D45245P	PERG	1F		ALL
2575B	24	Y2	CZ		6-7	31-62-15	D45245P	A14			D02179A	H15			YC051-YC058
2575B	24	Y2	CZ		6-10	31-62-15	D45245P	A14			D02179A	H15			YC059-YR328
2575R	24	Y2	CZ		0-0	31-62-15	D45245P	A13			D02179A	G15			ALL
2575Z			CZ		0-0	31-62-15	D45245P	PERG	1F		GB00523	ST..	1A		ALL
2576B	24	Y2	DA		5-5	31-62-15	D45245P	A16			D03261A	H15			YC051-YC058
2576B	24	Y2	DA		6-2	31-62-15	D45245P	A16			D03261A	H15			YC059-YR328
2576R	24	Y2	DA		0-0	31-62-15	D45245P	A15			D03261A	G15			ALL
2576Z			DA		0-0	31-62-15	D45245P	PERG	1F		GB00521	ST..	1A		ALL
2577B	24	Y2	DB		5-1	31-62-15	D45245P	B18			D03693A	G13			YC051-YC058
2577B	24	Y2	DB		5-4	31-62-15	D45245P	B18			D03693A	G13			YC059-YR328
2577R	24	Y2	DB		0-0	31-62-15	D45245P	B17			D03693A	F13			ALL
2577Z			DB		0-0	31-62-15	D45245P	PERG	1F		D03693A	PERG	1A		ALL
2578B	24	Y2	DC		6-11	31-62-15	D45245P	B20			D03687A	G15			YC051-YC058
2578B	24	Y2	DC		7-2	31-62-15	D45245P	B20			D03687A	G15			YC059-YR328
2578R	24	Y2	DC		0-0	31-62-15	D45245P	B19			D03687A	F15			ALL
2578Z			DC		0-0	31-62-15	D45245P	PERG	1F		D03687A	PERG	1A		ALL
2579B	24	Y2	DD		3-9	34-31-11	D41251J	4			D02179A	H01			YC051-YC058
2579B	24	Y2	DD		4-0	34-31-11	D41251J	4			D02179A	H01			YC059-YR328
2579R	24	Y2	DD		0-0	34-31-11	D41251J	3			D02179A	G01			ALL
2579Z			DD		0-0	34-31-11	D41251J	S/R			GB00523	ST..	1A		ALL
2580B	24	Y2	DE		4-5	34-31-11	D41251J	6			D03261A	H01			YC051-YC058
2580B	24	Y2	DE		4-8	34-31-11	D41251J	6			D03261A	H01			YC059-YR328
2580R	24	Y2	DE		0-0	34-31-11	D41251J	5			D03261A	G01			ALL
2580Z			DE		0-0	34-31-11	D41251J	S/R			GB00522	ST..	1A		ALL
2581B	24	Y2	DF		3-9	34-51-11	D41251J	8			D02179A	B01			YC051-YC058
2581B	24	Y2	DF		4-0	34-51-11	D41251J	8			D02179A	B01			YC059-YR328
2581R	24	Y2	DF		0-0	34-51-11	D41251J	7			D02179A	A01			ALL
2581Z			DF		0-0	34-51-11	D41251J	S/R			GB00523	ST..	1A		ALL
2582B	24	Y2	DG		4-5	34-51-11	D41251J	10			D03261A	B01			YC051-YC058
2582B	24	Y2	DG		4-8	34-51-11	D41251J	10			D03261A	B01			YC059-YR328
2582R	24	Y2	DG		0-0	34-51-11	D41251J	9			D03261A	A01			ALL
2582Z			DG		0-0	34-51-11	D41251J	S/R			GB00522	ST..	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0520

Page 22

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521		286A0521					E5-2 SHELF WIRE BUNDLE #1 (continued)									
2583B		24		Y2	DH	1-11	34-21-14	TB0523Z	B017	1A		TB0523Z	B021	1A		ALL
2583R		24		Y2	DH	0-0	34-21-14	TB0523Z	A017	1A		TB0523Z	A021	1A		ALL
2583Z					DH	0-0	34-21-14	TB0523Z	DED			TB0523Z	DED			ALL
2584B		24		Y2	DI	6-7	34-21-12	D03687A	E10			D45239P	A02			YC051-YC058
2584B		24		Y2	DI	6-10	34-21-12	D03687A	E10			D45239P	A02			YC059-YR328
2584R		24		Y2	DI	0-0	34-21-12	D03687A	D10			D45239P	A01			ALL
2584Z					DI	0-0	34-21-12	D03687A	PERG	1A		D45239P	PERG	1F		ALL
2585B		24		Y2	DJ	2-5	22-31-52	D02179A	H05			TB0522Y	B015	1A		ALL
2585R		24		Y2	DJ	0-0	22-31-52	D02179A	G05			TB0522Y	A015	1A		ALL
2585Z					DJ	0-0	22-31-52	D02179A	DED			GB00522	ST..	1A		ALL
2586B		24		Y2	DK	5-3	22-31-52	D45255P	B04			TB0522Y	B015	1A		YC051-YC058
2586B		24		Y2	DK	6-0	22-31-52	D45255P	B04			TB0522Y	B015	1A		YC059-YR328
2586R		24		Y2	DK	0-0	22-31-52	D45255P	B03			TB0522Y	A015	1A		ALL
2586Z					DK	0-0	22-31-52	D45255P	PERG	1F		GB00522	ST..	1A		ALL
2587B		24		Y2	DL	2-6	34-55-11	D02179A	E01			TB0522Y	B017	1A		ALL
2587R		24		Y2	DL	0-0	34-55-11	D02179A	D01			TB0522Y	A017	1A		ALL
2587Z					DL	0-0	34-55-11	D02179A	DED			GB00522	ST..	1A		ALL
2588B		24		Y2	DM	2-1	34-55-11	D03261A	E01			TB0522Y	B017	1A		ALL
2588R		24		Y2	DM	0-0	34-55-11	D03261A	D01			TB0522Y	A017	1A		ALL
2588Z					DM	0-0	34-55-11	D03261A	DED			GB00522	ST..	1A		ALL
2589B		24		Y2	DN	4-1	34-55-11	TB0522Y	B017	1A		D41251J	12			YC051-YC058
2589B		24		Y2	DN	4-5	34-55-11	TB0522Y	B017	1A		D41251J	12			YC059-YR328
2589R		24		Y2	DN	0-0	34-55-11	TB0522Y	A017	1A		D41251J	11			ALL
2589Z					DN	0-0	34-55-11	GB00522	ST..	1A		D41251J	S/R			ALL
2590B		24		Y2	DP	5-2	31-22-11	D03261B	E03			D41561P	B13			YC051-YC058
2590B		24		Y2	DP	5-5	31-22-11	D03261B	E03			D41561P	B13			YC059-YR328
2590R		24		Y2	DP	0-0	31-22-11	D03261B	D03			D41561P	A13			ALL
2590Z					DP	0-0	31-22-11	GB00521	ST..	1A		D41561P	PERG	1F		ALL
2591B		24		Y2	DQ	2-4	31-22-11	D02179B	E03			TB0522Y	B013	1A		ALL
2591R		24		Y2	DQ	0-0	31-22-11	D02179B	D03			TB0522Y	A013	1A		ALL
2591Z					DQ	0-0	31-22-11	GB00523	ST..	1A		GB00522	ST..	1A		ALL
2592B		24		Y2	DR	1-10	34-61-22	D02179A	B09			TB0523Y	B005	1A		ALL
2592R		24		Y2	DR	0-0	34-61-22	D02179A	A09			TB0523Y	A005	1A		ALL
2592Z					DR	0-0	34-61-22	D02179A	DED			GB00523	ST..	1A		ALL
2593B		24		Y2	DS	1-10	34-61-14	D02179A	H09			TB0523Y	B007	1A		ALL
2593R		24		Y2	DS	0-0	34-61-14	D02179A	G09			TB0523Y	A007	1A		ALL
2593Z					DS	0-0	34-61-14	D02179A	DED			GB00523	ST..	1A		ALL
2594B		24		Y2	DT	1-8	34-61-14	D02179B	E07			TB0523Y	B001	1A		ALL
2594R		24		Y2	DT	0-0	34-61-14	D02179B	D07			TB0523Y	A001	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0520

Page 23

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice Effectivity
W0521	286A0521	E5-2 SHELF WIRE BUNDLE #1 (continued)		
2594Z		DT	0-0 34-61-14 D02179B DED	GB00523 ST.. 1A ALL
2595B	22	X2 DU	1-11 34-61-15 D02179A B11	TB0523Y B011 1A ALL
2595R	22	X2 DU	0-0 34-61-15 D02179A A11	TB0523Y A011 1A ALL
2595Z		DU	0-0 34-61-15 D02179A DED	GB00523 ST.. 1A ALL
2596B	22	X2 DV	2-2 34-61-18 D03261A E09	TB0522Y B021 1A YC051-YC058
2596R	22	X2 DV	0-0 34-61-18 D03261A D09	TB0522Y A021 1A YC051-YC058
2596Z		DV	0-0 34-61-18 D03261A DED	GB00522 ST.. 1A YC051-YC058
2597B	24	Y2 DW	2-0 22-31-52 D03261A H05	TB0522Y B015 1A ALL
2597R	24	Y2 DW	0-0 22-31-52 D03261A G05	TB0522Y A015 1A ALL
2597Z		DW	0-0 22-31-52 D03261A DED	GB00522 ST.. 1A ALL
2598B	24	Y2 DX	5-2 31-22-11 D41561P B12	TB0522Y B013 1A YC051-YC058
2598B	24	Y2 DX	5-5 31-22-11 D41561P B12	TB0522Y B013 1A YC059-YR328
2598R	24	Y2 DX	0-0 31-22-11 D41561P A12	TB0522Y A013 1A ALL
2598Z		DX	0-0 31-22-11 D41561P PERG 1F	GB00522 ST.. 1A ALL
2599B	24	Y2 DY	5-2 31-22-11 D41561P B08	TB0522Y B013 1A YC051-YC058
2599B	24	Y2 DY	5-5 31-22-11 D41561P B08	TB0522Y B013 1A YC059-YR328
2599R	24	Y2 DY	0-0 31-22-11 D41561P A08	TB0522Y A013 1A ALL
2599Z		DY	0-0 31-22-11 D41561P PERG 1F	GB00522 ST.. 1A ALL
2604B	24	Y2 ID	6-1 34-21-14 D45239P A14	TB0523Z B021 1A YC051-YC052
2604B	24	Y2 ID	7-1 34-21-14 D45247P B14	TB0523Z B021 1A YC053-YC058
2604B	24	Y2 ID	7-4 34-21-14 D45247P B14	TB0523Z B021 1A YC059-YR328
2604R	24	Y2 ID	0-0 34-21-14 D45239P A13	TB0523Z A021 1A YC051-YC052
2604R	24	Y2 ID	0-0 34-21-14 D45247P B13	TB0523Z A021 1A YC053-YR328
2604Z		ID	0-0 34-21-14 D45239P PERG 1F	GB00523 ST.. 1A YC051-YC052
2604Z		ID	0-0 34-21-14 D45247P PERG 1F	GB00523 ST.. 1A YC053-YR328
2608B	24	Y2 IH	3-11 34-58-11 D41251J 26	TB0522Z B009 1A YC051-YC055
2608B	24	Y2 IH	3-11 34-58-11 D41251J 26	TB0522Y B009 1A YC056-YC058
2608B	24	Y2 IH	4-3 34-58-11 D41251J 26	TB0522Y B009 1A YC059-YR328
2608R	24	Y2 IH	0-0 34-58-11 D41251J 25	TB0522Z A009 1A YC051-YC055
2608R	24	Y2 IH	0-0 34-58-11 D41251J 25	TB0522Y A009 1A YC056-YR328
2608Z		IH	0-0 34-58-11 D41251J S/R	GB00522 ST.. 1A ALL
2610B	24	Y2 IJ	4-10 34-58-11 D03687B J03	SM00060 W YC051-YC058
2610B	24	Y2 IJ	5-0 34-58-11 D03687B J03	SM00060 W YC059-YD158
2610R	24	Y2 IJ	0-0 34-58-11 D03687B J02	SM00059 W YC051-YD158
2610Z		IJ	0-0 34-58-11 D03687B PERG 1A	SM00061 W YC051-YD158
2611B	24	Y2 IK	6-9 34-58-11 D41251J 28	SM00060 W YC051-YC058
2611B	24	Y2 IK	7-2 34-58-11 D41251J 28	SM00060 W YC059-YD158
2611B	24	Y2 IK	3-7 34-58-11 D41251J 28	TB0524Y B011 1A YL951-YR328
2611R	24	Y2 IK	0-0 34-58-11 D41251J 27	SM00059 W YC051-YD158

WIRE LIST

D280A108

91-21-11

Section W0520

Page 24

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521	286A0521			E5-2 SHELF WIRE BUNDLE #1 (continued)												
2611R	24	Y2	IK		0-0	34-58-11		D41251J	27			TB0524Y	A011	1A		YL951-YR328
2611Z			IK		0-0	34-58-11		D41251J	S/R			SM00061		W		YC051-YD158
2611Z			IK		0-0	34-58-11		D41251J	S/R			GB00524	ST..	1A		YL951-YR328
2614B	24	Y2	IN		4-3	34-58-11		D41251J	30			D03261B	B01			YC051-YC058
2614B	24	Y2	IN		4-7	34-58-11		D41251J	30			D03261B	B01			YC059-YR328
2614R	24	Y2	IN		0-0	34-58-11		D41251J	29			D03261B	A01			ALL
2614Z			IN		0-0	34-58-11		D41251J	S/R			GB00521	ST..	1A		ALL
2615B	24	Y2	IP		2-3	34-58-11		D02179B	B01			TB0522Z	B009	1A		YC051-YC055
2615B	24	Y2	IP		2-3	34-58-11		D02179B	B01			TB0522Y	B009	1A		YC056-YR328
2615R	24	Y2	IP		0-0	34-58-11		D02179B	A01			TB0522Z	A009	1A		YC051-YC055
2615R	24	Y2	IP		0-0	34-58-11		D02179B	A01			TB0522Y	A009	1A		YC056-YR328
2615Z			IP		0-0	34-58-11		GB00524	ST..	1A		GB00522	ST..	1A		ALL
2616B	24	Y2	IQ		4-10	34-58-11		D45225P	A12			TB0522Z	B009	1A		YC051-YC055
2616B	24	Y2	IQ		4-10	34-58-11		D45225P	A12			TB0522Y	B009	1A		YC056-YC058
2616B	24	Y2	IQ		5-1	34-58-11		D45225P	A12			TB0522Y	B009	1A		YC059-YR328
2616R	24	Y2	IQ		0-0	34-58-11		D45225P	A11			TB0522Z	A009	1A		YC051-YC055
2616R	24	Y2	IQ		0-0	34-58-11		D45225P	A11			TB0522Y	A009	1A		YC056-YR328
2616Z			IQ		0-0	34-58-11		D45225P	PERG	1F		GB00522	ST..	1A		ALL
2617B	24	Y2	IR		1-7	34-58-11		D45225P	B12			SM00060		W		YC051-YC058
2617B	24	Y2	IR		2-2	34-58-11		D45225P	B12			SM00060		W		YC059-YD158
2617B	24	Y2	IR		8-4	34-31-11		D45225P	B12			D41251J	39			YL951-YR328
2617R	24	Y2	IR		0-0	34-58-11		D45225P	B11			SM00059		W		YC051-YD158
2617R	24	Y2	IR		0-0	34-31-11		D45225P	B11			D41251J	38			YL951-YR328
2617Z			IR		0-0	34-58-11		D45225P	PERG	1F		SM00061		W		YC051-YD158
2617Z			IR		0-0	34-31-11		D45225P	PERG	1F		D41251J	S/R			YL951-YR328
2618B	24	Y2	IS		7-0	34-58-21		D41453J	32			SM00060		W		YC051-YC058
2618B	24	Y2	IS		7-4	34-58-21		D41453J	32			SM00060		W		YC059-YD158
2618R	24	Y2	IS		0-0	34-58-21		D41453J	31			SM00059		W		YC051-YD158
2618Z			IS		0-0	34-58-21		D41453J	S/R			SM00061		W		YC051-YD158
2619B	24	Y2	IT		5-0	34-21-22		D03693A	J08			D45239P	B03			YC061-YR328
2619R	24	Y2	IT		0-0	34-21-22		D03693A	H08			D45239P	B02			YC061-YR328
2619Z			IT		0-0	34-21-22		D03693A	PERG	1A		D45239P	PERG	1F		YC061-YR328
2623B	24	Y2	IX		7-5	34-61-21		D45211P	B11			D03263		W		YC051-YC058
2623B	24	Y2	IX		7-11	34-61-21		D45211P	B11			D03263		W		YC059-YR328
2623R	24	Y2	IX		0-0	34-61-21		D45211P	A11			D03263		V		ALL
2623Z			IX		0-0	34-61-21		D45211P	PERG	1F		D03263		DED		ALL
2624B	24	Y2	IY		3-5	34-61-21		D03267				D02179B	B09			YC051-YC058
2624B	24	Y2	IY		3-8	34-61-21		D03267				D02179B	B09			YC059-YR328
2624R	24	Y2	IY		0-0	34-61-21		D03267		V		D02179B	A09			ALL

WIRE LIST

D280A108

91-21-11

Section W0520

Page 25

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521	286A0521				E5-2 SHELF WIRE BUNDLE #1 (continued)										
2624Z				IY	0-0	34-61-21	D03267	DED			GB00523	ST..	1A		ALL
2625B	24	Y2		IZ	3-5	34-61-21	D03267	B			D02179B	H03			YC051-YC058
2625B	24	Y2		IZ	3-8	34-61-21	D03267	B			D02179B	H03			YC059-YR328
2625R	24	Y2		IZ	0-0	34-61-21	D03267	A			D02179B	G03			ALL
2625Z				IZ	0-0	34-61-21	D03267	DED			GB00523	ST..	1A		ALL
2628B	24	Y2		JC	4-4	34-61-11	D05925P	A07			TB0521Y	B003	1A		YC051-YC058
2628B	24	Y2		JC	4-7	34-61-11	D05925P	A07			TB0521Y	B003	1A		YC059-YR328
2628R	24	Y2		JC	0-0	34-61-11	D05925P	A06			TB0521Y	A003	1A		ALL
2628Z				JC	0-0	34-61-11	D05925P	PERG	1F		GB00521	ST..	1A		ALL
2629B	24	Y2		JD	2-3	23-27-11	D45225P	B16			D45211P	B06			YC051-YC058
2629B	24	Y2		JD	2-9	23-27-11	D45225P	B16			D45211P	B06			YC059-YD157, YN501-YR320
2629B	24	Y2		JD	2-9	23-27-39	D45225P	B16			D45211P	B06			YD158-YN260, YR321-YR328
2629R	24	Y2		JD	0-0	23-27-11	D45225P	B15			D45211P	A06			YC051-YD157, YN501-YR320
2629R	24	Y2		JD	0-0	23-27-39	D45225P	B15			D45211P	A06			YD158-YN260, YR321-YR328
2629Z				JD	0-0	23-27-11	D45225P	PERG	1F		D45211P	PERG	1F		YC051-YD157, YN501-YR320
2629Z				JD	0-0	23-27-39	D45225P	PERG	1F		D45211P	PERG	1F		YD158-YN260, YR321-YR328
2630B	24	Y2		JE	2-6	34-61-23	D45211P	B12			SM00079		W		YC051-YC058
2630B	24	Y2		JE	3-0	34-61-23	D45211P	B12			SM00079		W		YC059-YD157
2630B	24	Y2		JE	2-8	34-61-23	D45211P	B12			D05925P	B02			YD158-YR328
2630R	24	Y2		JE	0-0	34-61-23	D45211P	A12			SM00078		W		YC051-YD157
2630R	24	Y2		JE	0-0	34-61-23	D45211P	A12			D05925P	B01			YD158-YR328
2630Z				JE	0-0	34-61-23	D45211P	PERG	1F		SM00080		W		YC051-YD157
2630Z				JE	0-0	34-61-23	D45211P	PERG	1F		D05925P	PERG	1F		YD158-YR328
2631B	24	Y2		JF	6-1	23-27-13	D05925P	B04			TB0524Y	B021	1A		YC051-YC058
2631B	24	Y2		JF	6-5	23-27-13	D05925P	B04			TB0524Y	B021	1A		YC059-YD157
2631R	24	Y2		JF	0-0	23-27-13	D05925P	B03			TB0524Y	A021	1A		YC051-YD157
2631Z				JF	0-0	23-27-13	D05925P	PERG	1F		GB00524	ST..	1A		YC051-YD157
2632B	24	Y2		JG	3-4	23-27-14	D03263	B			TB0524Y	B021	1A		YC051-YC058
2632B	24	Y2		JG	3-7	23-27-14	D03263	B			TB0524Y	B021	1A		YC059-YD157
2632B	24	Y2		JG	6-3	23-27-35	D03263	B			SM00072		W		YD158-YR328
2632R	24	Y2		JG	0-0	23-27-14	D03263	A			TB0524Y	A021	1A		YC051-YD157
2632R	24	Y2		JG	0-0	23-27-35	D03263	A			SM00071		W		YD158-YR328
2632Z				JG	0-0	23-27-14	D03263	DED			GB00524	ST..	1A		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0520

Page 26

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From				To				Effectivity		
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip		Term	Type
W0521	286A0521			E5-2 SHELF WIRE BUNDLE #1 (continued)											
2632Z			JG	0-0	23-27-35	D03263	DED				SM00073		W		YD158-YR328
2633B	24	Y2	JH	6-10	23-27-14	D45211P	B08				TB0524Y	B021	1A		YC051-YC058
2633B	24	Y2	JH	7-1	23-27-14	D45211P	B08				TB0524Y	B021	1A		YC059-YD157
2633R	24	Y2	JH	0-0	23-27-14	D45211P	A08				TB0524Y	A021	1A		YC051-YD157
2633Z			JH	0-0	23-27-14	D45211P	PERG	1F			GB00524	ST..	1A		YC051-YD157
2637B	24	Y2	JL	4-7	34-61-11	D45235P	B17				TB0521Y	B003	1A		YC051-YC058
2637B	24	Y2	JL	4-10	34-61-11	D45235P	B17				TB0521Y	B003	1A		YC059-YR328
2637R	24	Y2	JL	0-0	34-61-11	D45235P	B14				TB0521Y	A003	1A		ALL
2637Z			JL	0-0	34-61-11	D45235P	PERG	1F			GB00521	ST..	1A		ALL
2638B	24	Y2	JM	4-0	34-61-11	D06063J	13				TB0521Y	B003	1A		YC051-YC058
2638B	24	Y2	JM	4-3	34-61-11	D06063J	13				TB0521Y	B003	1A		YC059-YR328
2638R	24	Y2	JM	0-0	34-61-11	D06063J	12				TB0521Y	A003	1A		ALL
2638Z			JM	0-0	34-61-11	D06063J	DED				GB00521	ST..	1A		ALL
2640B	24	Y2	JO	5-3	34-61-22	D45235P	B20				TB0523Y	B005	1A		YC051-YC058
2640B	24	Y2	JO	6-0	34-61-22	D45235P	B20				TB0523Y	B005	1A		YC059-YR328
2640R	24	Y2	JO	0-0	34-61-22	D45235P	B18				TB0523Y	A005	1A		ALL
2640Z			JO	0-0	34-61-22	D45235P	PERG	1F			GB00523	ST..	1A		ALL
2643B	24	Y2	JS	1-11	34-61-22	D05925P	A04				D45255P	A20			YC051-YC058
2643B	24	Y2	JS	2-3	34-61-22	D05925P	A04				SM00115		W		YC059-YR328
2643R	24	Y2	JS	0-0	34-61-22	D05925P	A03				D45255P	A19			YC051-YC058
2643R	24	Y2	JS	0-0	34-61-22	D05925P	A03				SM00114		W		YC059-YR328
2643Z			JS	0-0	34-61-22	D05925P	PERG	1F			D45255P	PERG	1F		YC051-YC058
2643Z			JS	0-0	34-61-22	D05925P	PERG	1F			SM00116		W		YC059-YR328
2644B	24	Y2	JT	2-10	34-61-22	D06063J	6				D45255P	B06			YC051-YC058
2644B	24	Y2	JT	3-4	34-61-22	D06063J	6				D45255P	B06			YC059-YR328
2644R	24	Y2	JT	0-0	34-61-22	D06063J	5				D45255P	B05			ALL
2644Z			JT	0-0	34-61-22	D06063J	DED				D45255P	PERG	1F		ALL
2645B	24	Y2	JU	1-9	31-35-02	D45261P	A10				D05925P	B06			YC051-YC058
2645B	24	Y2	JU	2-3	31-35-02	D45261P	A10				D05925P	B06			YC059-YN260
2645B	24	Y2	JU	2-3	31-35-02	D05925P	B06				D45261P	A10			YN501-YR328
2645R	24	Y2	JU	0-0	31-35-02	D45261P	A09				D05925P	B05			YC051-YN260
2645R	24	Y2	JU	0-0	31-35-02	D05925P	B05				D45261P	A09			YN501-YR328
2645Z			JU	0-0	31-35-02	D45261P	PERG	1F			D05925P	PERG	1F		YC051-YN260
2645Z			JU	0-0	31-35-02	D05925P	PERG	1F			D45261P	PERG	1F		YN501-YR328
2646B	24	Y2	JV	1-11	23-32-21	D45261P	A20				D45225P	A20			YC051-YC058
2646B	24	Y2	JV	2-5	23-32-21	D45261P	A20				D45225P	A20			YC059-YD157
2646R	24	Y2	JV	0-0	23-32-21	D45261P	A19				D45225P	A19			YC051-YD157
2646Z			JV	0-0	23-32-21	D45261P	PERG	1F			D45225P	PERG	1F		YC051-YD157
2647B	24	Y2	JW	6-4	34-61-14	D45265P	B13				TB0523Z	B013	1A		YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0520

Page 27

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521	286A0521			E5-2 SHELF WIRE BUNDLE #1 (continued)											
2647R	24	Y2	JW		0-0	34-61-14	D45265P	A13			TB0523Z	A013	1A		YD158-YD170
2647Z			JW		0-0	34-61-14	D45265P	PERG	1F		GB00523	ST..	1A		YD158-YD170
2648B	24	Y2	JX		5-3	34-61-15	D45245P	A06			TB0522Y	B011	1A		YC056-YC058
2648B	24	Y2	JX		6-0	34-61-15	D45245P	A06			TB0522Y	B011	1A		YC059-YR328
2648R	24	Y2	JX		0-0	34-61-15	D45245P	A05			TB0522Y	A011	1A		YC056-YR328
2648Z			JX		0-0	34-61-15	D45245P	PERG	1F		GB00522	ST..	1A		YC056-YR328
2649B	24	Y2	JY		2-7	34-61-15	D03425	K			TB0522Y	B011	1A		YC056-YC058
2649B	24	Y2	JY		2-10	34-61-15	D03425	K			TB0522Y	B011	1A		YC059-YD170, YN501-YR328
2649B	24	Y2	JY		2-10	34-61-15	D03425	K			TB0522Y	B011	%A		YL951-YN260
2649R	24	Y2	JY		0-0	34-61-15	D03425	J			TB0522Y	A011	1A		YC056-YD170, YN501-YR328
2649R	24	Y2	JY		0-0	34-61-15	D03425	J			TB0522Y	A011	%A		YL951-YN260
2649Z			JY		0-0	34-61-15	D03425	DED			GB00522	ST..	1A		YC056-YR328
2650B	24	Y2	JZ		6-4	34-61-15	D45265P	B14			TB0524Y	B003	1A		YD158-YD170
2650R	24	Y2	JZ		0-0	34-61-15	D45265P	A14			TB0524Y	A003	1A		YD158-YD170
2650Z			JZ		0-0	34-61-15	D45265P	PERG	1F		TB0524Y	DED			YD158-YD170
2651B	24	Y2	KA		2-1	23-27-32	D05925P	B04			SM00072		W		YD158-YR328
2651R	24	Y2	KA		0-0	23-27-32	D05925P	B03			SM00071		W		YD158-YR328
2651Z			KA		0-0	23-27-32	D05925P	PERG	1F		SM00073		W		YD158-YR328
2652B	24	Y2	KB		2-9	23-27-32	D45211P	B08			SM00072		W		YD158-YR328
2652R	24	Y2	KB		0-0	23-27-32	D45211P	A08			SM00071		W		YD158-YR328
2652Z			KB		0-0	23-27-32	D45211P	PERG	1F		SM00073		W		YD158-YR328
2653B	24	Y2	KC		4-8	23-27-32	SM00072		W		D02179B	REF	VP		YD158-YN260
2653R	24	Y2	KC		0-0	23-27-32	SM00071		W		D02179B	REF	VP		YD158-YN260
2653Z			KC		0-0	23-27-32	SM00073		W		D02179B	DED			YD158-YN260
2654B	24	Y2	KD		6-11	23-27-32	D45211P	B14			D02179B	REF	VP		YD158-YN260
2654R	24	Y2	KD		0-0	23-27-32	D45211P	A14			D02179B	REF	VP		YD158-YN260
2654Z			KD		0-0	23-27-32	D45211P	PERG	1F		D02179B	DED			YD158-YN260
2656B	22	X2	KF		2-0	49-62-11	D45225P	B19			D45265P	A12			YC051-YC058
2656B	22	X2	KF		2-6	49-62-11	D45225P	B19			D45265P	A12			YC059-YR328
2656R	22	X2	KF		0-0	49-62-11	D45225P	B18			D45265P	A11			ALL
2656Z			KF		0-0	49-62-11	D45225P	PERG	1F		D45265P	PERG	1F		ALL
2657B	22	X2	KG		2-10	34-61-18	D45001P	B07			SM00070		W		YC051-YC058
2657B	22	X2	KG		3-4	31-32-15	D45001P	B07			SM00070		W		YC059-YD157
2657R	22	X2	KG		0-0	34-61-18	D45001P	A07			SM00069		W		YC051-YC058
2657R	22	X2	KG		0-0	31-32-15	D45001P	A07			SM00069		W		YC059-YD157
2657Z			KG		0-0	34-61-18	D45001P	PERG	1F		SM00077		W		YC051-YC058
2657Z			KG		0-0	31-32-15	D45001P	PERG	1F		SM00077		W		YC059-YD157

WIRE LIST

D280A108

91-21-11

Section W0520

Page 28

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				Effectivity	
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W0521	286A0521			E5-2 SHELF WIRE BUNDLE #1 (continued)												
2662B	24		Y2	KL	6-11	34-61-25	D02179B	CAP	Y		D45211P	B03			YD158-YN260	
2662R	24		Y2	KL	0-0	34-61-25	D02179B	CAP	Y		D45211P	A03			YD158-YN260	
2662Z				KL	0-0	34-61-25	D02179B	DED			D45211P	PERG	1F		YD158-YN260	
2663B	24		Y2	KM	6-11	34-61-25	D02179B	CAP	Y		D45211P	B04			YD158-YN260	
2663R	24		Y2	KM	0-0	34-61-25	D02179B	CAP	Y		D45211P	A04			YD158-YN260	
2663Z				KM	0-0	34-61-25	D02179B	DED			D45211P	PERG	1F		YD158-YN260	
2664B	24		Y2	KN	6-11	34-61-25	D02179B	CAP	Y		D45211P	B05			YD158-YN260	
2664R	24		Y2	KN	0-0	34-61-25	D02179B	CAP	Y		D45211P	A05			YD158-YN260	
2664Z				KN	0-0	34-61-25	D02179B	DED			D45211P	PERG	1F		YD158-YN260	
2665B	24		Y2	KP	6-4	34-61-24	D02179B	H02			D41561P	B20			YC051-YC058	
2665B	24		Y2	KP	6-7	34-61-24	D02179B	H02			D41561P	B20			YC059-YD157	
2665B	24		Y2	KP	6-7	34-61-24	D41561P	B20			D02179B	H02			YD158-YR328	
2665R	24		Y2	KP	0-0	34-61-24	D02179B	G02			D41561P	A20			YC051-YD157	
2665R	24		Y2	KP	0-0	34-61-24	D41561P	A20			D02179B	G02			YD158-YR328	
2665Z				KP	0-0	34-61-24	GB00524	ST..	1A		D41561P	PERG	1F		YC051-YD157	
2665Z				KP	0-0	34-61-24	D41561P	PERG	1F		D02179B	DED			YD158-YR328	
2666B	24		Y2	KQ	6-3	31-33-01	D02179B	B08			D45261P	B06			YC051-YC058	
2666B	24		Y2	KQ	6-6	31-33-01	D02179B	B08			D45261P	B06			YC059-YR328	
2666R	24		Y2	KQ	0-0	31-33-01	D02179B	A08			D45261P	A03			ALL	
2666Z				KQ	0-0	31-33-01	GB00524	ST..	1A		D45261P	PERG	1F		ALL	
2667B	24		Y2	KR	3-1	34-61-23	D45001P	B08			SM00079		W		YC051-YC058	
2667B	24		Y2	KR	3-7	34-61-23	D45001P	B08			SM00079		W		YC059-YD157	
2667R	24		Y2	KR	0-0	34-61-23	D45001P	A08			SM00078		W		YC051-YD157	
2667Z				KR	0-0	34-61-23	D45001P	PERG	1F		SM00080		W		YC051-YD157	
2668B	24		Y2	KS	1-9	34-61-23	D05925P	B02			SM00079		W		YC051-YC058	
2668B	24		Y2	KS	2-3	34-61-23	D05925P	B02			SM00079		W		YC059-YD157	
2668R	24		Y2	KS	0-0	34-61-23	D05925P	B01			SM00078		W		YC051-YD157	
2668Z				KS	0-0	34-61-23	D05925P	PERG	1F		SM00080		W		YC051-YD157	
2669B	24		Y2	KT	1-9	23-15-15	D05925P	A09			SM00082		W		YC051-YC058	
2669B	24		Y2	KT	2-3	23-15-15	D05925P	A09			SM00082		W		YC059-YD157	
2669R	24		Y2	KT	0-0	23-15-15	D05925P	A08			SM00081		W		YC051-YD157	
2669Z				KT	0-0	23-15-15	D05925P	PERG	1F		SM00083		W		YC051-YD157	
2670B	24		Y2	KU	2-8	23-15-15	D08105P	A09			SM00082		W		YC051-YC058	
2670B	24		Y2	KU	3-2	23-15-15	D08105P	A09			SM00082		W		YC059-YD157	
2670R	24		Y2	KU	0-0	23-15-15	D08105P	A08			SM00081		W		YC051-YD157	
2670Z				KU	0-0	23-15-15	D08105P	PERG	1F		SM00083		W		YC051-YD157	
2671B	24		Y2	KV	3-1	23-15-15	D45001P	B09			SM00082		W		YC051-YC058	
2671B	24		Y2	KV	3-7	23-15-15	D45001P	B09			SM00082		W		YC059-YD157	
2671R	24		Y2	KV	0-0	23-15-15	D45001P	A09			SM00081		W		YC051-YD157	

WIRE LIST

D280A108

91-21-11

Section W0520

Page 29

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521	286A0521				E5-2 SHELF WIRE BUNDLE #1 (continued)										
2671Z				KV	0-0	23-15-15	D45001P	PERG	1F		SM00083		W		YC051-YD157
2672B	24	Y2		KW	2-11	23-15-15	D45225P	B14			D45001P	B06			YC051-YC058
2672B	24	Y2		KW	3-5	23-15-15	D45225P	B14			D45001P	B06			YC059-YD157
2672R	24	Y2		KW	0-0	23-15-15	D45225P	B13			D45001P	A06			YC051-YD157
2672Z				KW	0-0	23-15-15	D45225P	PERG	1F		D45001P	PERG	1F		YC051-YD157
2673B	24	Y2		KX	3-1	34-21-13	D45001P	B04			SM00085		W		YC051-YC058
2673B	24	Y2		KX	3-7	34-21-13	D45001P	B04			SM00085		W		YC059-YD157
2673R	24	Y2		KX	0-0	34-21-13	D45001P	A04			SM00084		W		YC051-YD157
2673Z				KX	0-0	34-21-13	D45001P	PERG	1F		SM00086		W		YC051-YD157
2674B	24	Y2		KY	4-4	34-21-13	SM00085		W		TB0524Z	B017	1A		YC051-YC058
2674B	24	Y2		KY	4-7	34-21-13	SM00085		W		TB0524Z	B017	1A		YC059-YD157
2674R	24	Y2		KY	0-0	34-21-13	SM00084		W		TB0524Z	A017	1A		YC051-YD157
2674Z				KY	0-0	34-21-13	SM00086		W		GB00524	ST..	1A		YC051-YD157
2677B	24	Y2		LB	6-8	34-21-14	D45367P	B04			TB0523Z	B017	1A		YL951-YN260
2677B	24	Y2		LB	6-8	34-21-14	D45319P	B04			TB0523Z	B017	1A		YN501-YR328
2677R	24	Y2		LB	0-0	34-21-14	D45367P	A04			TB0523Z	A017	1A		YL951-YN260
2677R	24	Y2		LB	0-0	34-21-14	D45319P	A04			TB0523Z	A017	1A		YN501-YR328
2677Z				LB	0-0	34-21-14	D45367P	PERG	1F		GB00523	ST..	1A		YL951-YN260
2677Z				LB	0-0	34-21-14	D45319P	PERG	1F		GB00523	ST..	1A		YN501-YR328
2678B	24	Y2		LC	6-8	34-61-15	D45261P	B10			TB0524Y	B021	1A		YD158-YD170
2678R	24	Y2		LC	0-0	34-61-15	D45261P	B09			TB0524Y	A021	1A		YD158-YD170
2678Z				LC	0-0	34-61-15	D45261P	PERG	1F		TB0524Y	DED			YD158-YD170
2679B	24	Y2		LD	3-9	34-21-13	D45367P	B05			SM00088		W		YL951-YL954, YN231-YN235
2679B	24	Y2		LD	4-0	34-21-13	D45367P	B05			SM00088		W		YL955-YL999, YN236-YN260
2679B	24	Y2		LD	4-0	34-21-13	D45319P	B03			SM00088		W		YN501-YR328
2679R	24	Y2		LD	0-0	34-21-13	D45367P	A05			SM00087		W		YL951-YN260
2679R	24	Y2		LD	0-0	34-21-13	D45319P	A03			SM00087		W		YN501-YR328
2679Z				LD	0-0	34-21-13	D45367P	PERG	1F		SM00090		W		YL951-YN260
2679Z				LD	0-0	34-21-13	D45319P	PERG	1F		SM00090		W		YN501-YR328
2680B	24	Y2		LE	3-2	34-21-13	SM00088		W		TB0524Z	B017	1A		YL951-YL954, YN231-YN235
2680B	24	Y2		LE	3-5	34-21-13	SM00088		W		TB0524Z	B017	1A		YL955-YL999, YN236-YR328
2680R	24	Y2		LE	0-0	34-21-13	SM00087		W		TB0524Z	A017	1A		YL951-YR328
2680Z				LE	0-0	34-21-13	SM00090		W		GB00524	ST..	1A		YL951-YR328
2681B	22	X2		LF	1-8	34-61-18	D45225P	A17			SM00070		W		YC051-YC058
2681B	22	X2		LF	2-2	31-32-15	D45225P	A17			SM00070		W		YC059-YR328

WIRE LIST

D280A108

91-21-11

Section W0520

Page 30

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521		286A0521			E5-2 SHELF WIRE BUNDLE #1 (continued)											
2681R		22		X2	LF	0-0	34-61-18	D45225P	A16			SM00069		W		YC051-YC058
2681R		22		X2	LF	0-0	31-32-15	D45225P	A16			SM00069		W		YC059-YR328
2681Z					LF	0-0	34-61-18	D45225P	PERG	1F		SM00077		W		YC051-YC058
2681Z					LF	0-0	31-32-15	D45225P	PERG	1F		SM00077		W		YC059-YR328
2684B		22		X2	LI	3-5	23-27-15	D45211P	B16			D45001P	B01			YC051-YC058
2684B		22		X2	LI	3-11	23-27-15	D45211P	B16			D45001P	B01			YC059-YD157
2684R		22		X2	LI	0-0	23-27-15	D45211P	A16			D45001P	A01			YC051-YD157
2684Z					LI	0-0	23-27-15	D45211P	PERG	1F		D45001P	PERG	1F		YC051-YD157
2685B		24		Y2	LJ	6-9	23-15-12	TB0522Y	B023	1A		D45001P	B02			YC051-YC058
2685B		24		Y2	LJ	7-0	23-15-12	TB0522Y	B023	1A		D45001P	B02			YC059-YD157
2685R		24		Y2	LJ	0-0	23-15-12	TB0522Y	A023	1A		D45001P	A02			YC051-YD157
2685Z					LJ	0-0	23-15-12	GB00522	ST..	1A		D45001P	PERG	1F		YC051-YD157
2690B		24		Y2	LP	2-8	23-15-15	D08105P	CAP	Y		SM00082		W		YC051-YC058
2690B		24		Y2	LP	3-2	23-15-15	D08105P	CAP	Y		SM00082		W		YC059-YD157
2690R		24		Y2	LP	0-0	23-15-15	D08105P	CAP	Y		SM00081		W		YC051-YD157
2690Z					LP	0-0	23-15-15	D08105P	DED			SM00083		W		YC051-YD157
2691B		24		Y2	LQ	2-8	23-15-15	D08105P	CAP	Y		SM00082		W		YC051-YC058
2691B		24		Y2	LQ	3-2	23-15-15	D08105P	CAP	Y		SM00082		W		YC059-YD157
2691R		24		Y2	LQ	0-0	23-15-15	D08105P	CAP	Y		SM00081		W		YC051-YD157
2691Z					LQ	0-0	23-15-15	D08105P	DED			SM00083		W		YC051-YD157
2692B		22		X2	LR	3-3	44-21-20	D45319P	B08			D45211P	B16			YN501-YR328
2692R		22		X2	LR	0-0	44-21-20	D45319P	A08			D45211P	A16			YN501-YR328
2692Z					LR	0-0	44-21-20	D45319P	PERG	1F		D45211P	PERG	1F		YN501-YR328
2693B		24		Y2	LS	6-6	34-61-15	D45261P	B10			D03423	K			YC056-YC058
2693B		24		Y2	LS	7-0	34-61-15	D45261P	B10			D03423	K			YC059-YD157
2693B		24		Y2	LS	7-4	34-61-15	D45367P	B02			D03423	K			YL951-YN260
2693B		24		Y2	LS	7-4	34-61-15	D45319P	B02			D03423	K			YN501-YR328
2693R		24		Y2	LS	0-0	34-61-15	D45261P	B09			D03423	J			YC056-YD157
2693R		24		Y2	LS	0-0	34-61-15	D45367P	A02			D03423	J			YL951-YN260
2693R		24		Y2	LS	0-0	34-61-15	D45319P	A02			D03423	J			YN501-YR328
2693Z					LS	0-0	34-61-15	D45261P	PERG	1F		D03423	DED			YC056-YD157
2693Z					LS	0-0	34-61-15	D45367P	PERG	1F		D03423	DED			YL951-YN260
2693Z					LS	0-0	34-61-15	D45319P	PERG	1F		D03423	DED			YN501-YR328
2694B		24		Y2	LT	1-10	34-61-18	D45261P	A13			SM00070		W		YC051-YC058
2694B		24		Y2	LT	2-7	31-32-15	D45261P	A13			SM00112		W		YC059-YR328
2694R		24		Y2	LT	0-0	34-61-18	D45261P	A12			SM00069		W		YC051-YC058
2694R		24		Y2	LT	0-0	31-32-15	D45261P	A12			SM00111		W		YC059-YR328
2694Z					LT	0-0	34-61-18	D45261P	PERG	1F		SM00077		W		YC051-YC058
2694Z					LT	0-0	31-32-15	D45261P	PERG	1F		SM00113		W		YC059-YR328

WIRE LIST

D280A108

91-21-11

Section W0520

Page 31

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521	286A0521			E5-2 SHELF WIRE BUNDLE #1 (continued)											
2695B	24		Y2	LU	6-2	23-15-12	D45211P	B17			TB0522Y	B023	1A		YC051-YC058
2695B	24		Y2	LU	6-5	23-15-12	D45211P	B17			TB0522Y	B023	1A		YC059-YD157
2695R	24		Y2	LU	0-0	23-15-12	D45211P	A17			TB0522Y	A023	1A		YC051-YD157
2695Z				LU	0-0	23-15-12	D45211P	PERG	1F		GB00522	ST..	1A		YC051-YD157
2696B	24		Y2	LV	2-6	23-15-12	D02179B	E06			TB0522Y	B023	1A		YC051-YD157
2696R	24		Y2	LV	0-0	23-15-12	D02179B	D06			TB0522Y	A023	1A		YC051-YD157
2696Z				LV	0-0	23-15-12	D02179B	DED			GB00522	ST..	1A		YC051-YD157
2697B	22		X2	LW	3-3	44-21-20	D45319P	B06			D45211P	B20			YN501-YR328
2697R	22		X2	LW	0-0	44-21-20	D45319P	A06			D45211P	A20			YN501-YR328
2697Z				LW	0-0	44-21-20	D45319P	PERG	1F		D45211P	PERG	1F		YN501-YR328
2699B	24		Y2	LY	2-1	23-15-12	D03261B	E06			TB0522Y	B023	1A		YC051-YD157
2699R	24		Y2	LY	0-0	23-15-12	D03261B	D06			TB0522Y	A023	1A		YC051-YD157
2699Z				LY	0-0	23-15-12	D03261B	DED			GB00522	ST..	1A		YC051-YD157
2901B	24		Y2	MA	3-5	34-21-13	D41251J	49			TB0523Y	B003	1A		YC051-YC058
2901B	24		Y2	MA	3-8	34-21-13	D41251J	49			TB0523Y	B003	1A		YC059-YD157
2901B	24		Y2	MA	3-5	34-21-13	D41251J	49			SM00043		W		YD158-YR328
2901R	24		Y2	MA	0-0	34-21-13	D41251J	48			TB0523Y	A003	1A		YC051-YD157
2901R	24		Y2	MA	0-0	34-21-13	D41251J	48			SM00042		W		YD158-YR328
2901Z				MA	0-0	34-21-13	D41251J	S/R			GB00524	ST..	1A		YC051-YC064
2901Z				MA	0-0	34-21-13	D41251J	S/R			GB00523	ST..	1A		YC065-YD157
2901Z				MA	0-0	34-21-13	D41251J	S/R			SM00044		W		YD158-YR328
2911B	24		Y2	MK	2-1	34-61-26	D05925P	B11			SM00070		W		YC059-YR328
2911R	24		Y2	MK	0-0	34-61-26	D05925P	A11			SM00069		W		YC059-YR328
2911Z				MK	0-0	34-61-26	D05925P	PERG	1F		SM00077		W		YC059-YR328
2913B	24		Y2	MM	5-1	34-61-18	D45293P	B02			TB0522Y	B019	1A		YC059-YR328
2913R	24		Y2	MM	0-0	34-61-18	D45293P	A02			TB0522Y	A019	1A		YC059-YR328
2913Z				MM	0-0	34-61-18	D45293P	PERG	1F		GB00522	ST..	1A		YC059-YR328
2914B	24		Y2	MN	2-5	34-61-18	D02179B	E09			TB0522Y	B019	1A		YC059-YR328
2914R	24		Y2	MN	0-0	34-61-18	D02179B	D09			TB0522Y	A019	1A		YC059-YR328
2914Z				MN	0-0	34-61-18	D02179B	DED			GB00522	ST..	1A		YC059-YR328
2915B	24		Y2	MP	2-0	34-61-18	D03261B	E09			TB0522Y	B019	1A		YC059-YR328
2915R	24		Y2	MP	0-0	34-61-18	D03261B	D09			TB0522Y	A019	1A		YC059-YR328
2915Z				MP	0-0	34-61-18	D03261B	DED			GB00522	ST..	1A		YC059-YR328
2916B	24		Y2	MQ	2-3	34-61-26	D45293P	A10			SM00115		W		YC059-YR328
2916R	24		Y2	MQ	0-0	34-61-26	D45293P	A09			SM00114		W		YC059-YR328
2916Z				MQ	0-0	34-61-26	D45293P	PERG	1F		SM00116		W		YC059-YR328
2917B	24		Y2	MR	8-2	22-11-53	D45293P	B04			D41251J	20			YC059-YR328
2917R	24		Y2	MR	0-0	22-11-53	D45293P	A04			D41251J	19			YC059-YR328
2917Z				MR	0-0	22-11-53	D45293P	PERG	1F		D41251J	S/R			YC059-YR328

WIRE LIST

D280A108

91-21-11

Section W0520

Page 32

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521		286A0521					E5-2 SHELF WIRE BUNDLE #1 (continued)									
2918B		24		Y2	MS	2-9	34-61-22	D45255P	A20			SM00115		W		YC059-YR328
2918R		24		Y2	MS	0-0	34-61-22	D45255P	A19			SM00114		W		YC059-YR328
2918Z					MS	0-0	34-61-22	D45255P	PERG	1F		SM00116		W		YC059-YR328
2919B		24		0N	MT	2-7	34-61-12	D02179B	E04			D03261B	H04			YC065-YR328
2919W		24		0N	MT	0-0	34-61-12	D02179B	D04			D03261B	G04			YC065-YR328
2919Z					MT	0-0	34-61-12	GB00524	ST..	1A		GB00522	ST..	1A		YC065-YR328
2920B		24		0N	MU	2-7	34-61-12	D02179B	H04			D03261B	E04			YC065-YR328
2920W		24		0N	MU	0-0	34-61-12	D02179B	G04			D03261B	D04			YC065-YR328
2920Z					MU	0-0	34-61-12	GB00524	ST..	1A		GB00522	ST..	1A		YC065-YR328
2921B		24		Y2	MV	3-5	34-21-13	D41251J	51			SM00043		W		YD158-YR328
2921R		24		Y2	MV	0-0	34-21-13	D41251J	50			SM00042		W		YD158-YR328
2921Z					MV	0-0	34-21-13	D41251J	S/R			SM00044		W		YD158-YR328
2922B		24		Y2	MW	1-0	34-21-13	SM00043		W		TB0523Y	B003	1A		YD158-YD170
2922R		24		Y2	MW	0-0	34-21-13	SM00042		W		TB0523Y	A003	1A		YD158-YD170
2922Z					MW	0-0	34-21-13	SM00044		W		GB00523	ST..	1A		YD158-YD170
2941B		24		Y2	NQ	2-7	23-27-39	D45293P	B06			D45211P	B09			YL951-YL954, YN231-YN235
2941R		24		Y2	NQ	0-0	23-27-39	D45293P	B05			D45211P	A09			YL951-YL954, YN231-YN235
2941Z					NQ	0-0	23-27-39	D45293P	PERG	1F		D45211P	PERG	1F		YL951-YL954, YN231-YN235
2942B		24		Y2	NR	2-7	23-27-39	D45293P	B08			D45211P	B13			YL951-YL954, YN231-YN235
2942R		24		Y2	NR	0-0	23-27-39	D45293P	B07			D45211P	A13			YL951-YL954, YN231-YN235
2942Z					NR	0-0	23-27-39	D45293P	PERG	1F		D45211P	PERG	1F		YL951-YL954, YN231-YN235
2943B		24		Y2	NS	2-7	23-27-39	D45293P	B10			D45211P	B17			YL951-YL954, YN231-YN235
2943R		24		Y2	NS	0-0	23-27-39	D45293P	B09			D45211P	A17			YL951-YL954, YN231-YN235
2943Z					NS	0-0	23-27-39	D45293P	PERG	1F		D45211P	PERG	1F		YL951-YL954, YN231-YN235
3001B		24		PM	GA	6-7	34-21-12	D03687A	H07			D45239P	A09			YC051-YC058
3001B		24		PM	GA	6-10	34-21-12	D03687A	H07			D45239P	A09			YC059-YR328
3001R		24		PM	GA	0-0	34-21-12	D03687A	J07			D45239P	A08			ALL
3001Y		24		PM	GA	0-0	34-21-12	D03687A	K07			D45239P	A10			ALL
3002B		22		PC	GB	1-11	27-32-11	D45239P	B07			D45261P	B04			YC051-YC058
3002B		22		PC	GB	2-5	27-32-11	D45239P	B07			D45261P	B04			YC059-YR328

WIRE LIST

D280A108

91-21-11

Section W0520

Page 33

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0521		286A0521			E5-2 SHELF WIRE BUNDLE #1 (continued)											
3002R		22		PC	GB	0-0	27-32-11	D45239P	B06			D45261P	B03			ALL
3002Y		22		PC	GB	0-0	27-32-11	D45239P	B08			D45261P	B05			ALL
3501B		22		X3	HA	6-2	34-21-12	D45239P	A04			TB0524Y	B013	1A		YC051-YC058
3501B		22		X3	HA	6-5	34-21-12	D45239P	A04			TB0524Y	B013	1A		YC059-YR328
3501R		22		X3	HA	0-0	34-21-12	D45239P	A03			TB0524Y	A013	1A		ALL
3501Y		22		X3	HA	0-0	34-21-12	D45239P	A05			TB0524Y	B015	1A		ALL
3501Z					HA	0-0	34-21-12	D45239P	PERG	1F		GB00524	ST..	1A		ALL
3502B		22		X3	HB	2-1	34-21-12	D03687A	H06			TB0524Y	B013	1A		ALL
3502R		22		X3	HB	0-0	34-21-12	D03687A	G06			TB0524Y	A013	1A		ALL
3502Y		22		X3	HB	0-0	34-21-12	D03687A	J06			TB0524Y	B015	1A		ALL
3502Z					HB	0-0	34-21-12	D03687A	PERG	1A		GB00524	ST..	1A		ALL
3503B		22		X3	HC	6-6	34-21-12	D45245P	A18			TB0524Y	B013	1A		YC051-YC058
3503B		22		X3	HC	6-9	34-21-12	D45245P	A18			TB0524Y	B013	1A		YC059-YR328
3503R		22		X3	HC	0-0	34-21-12	D45245P	A17			TB0524Y	A013	1A		ALL
3503Y		22		X3	HC	0-0	34-21-12	D45245P	A19			TB0524Y	B015	1A		ALL
3503Z					HC	0-0	34-21-12	D45245P	PERG	1F		GB00524	ST..	1A		ALL
W0523		286A0523			E5-2 SHELF WIRE BUNDLE #2											
0301		20		PA		2-10	34-61-11	D45247P	A20			D08105P	A01			ALL
0302		22		PA		5-2	34-61-11	D08105P	A02			SM00053		W		ALL
0303		22		PA		2-6	34-61-11	D02179A	J13			SM00053		W		ALL
0304		22		PA		1-10	34-61-11	D03261A	J13			SM00053		W		ALL
0305		20		PA		1-9	34-61-11	D03261C	7			GD05205	AC..	E		YC051-YD153
0305		20		PA		1-9	34-61-11	D03261C	7			GD05205	AC..	E	*3	YD154-YR328
0306		20		PA		1-9	34-61-11	D03261C	8			GD05206	DC..	E		ALL
0307		20		PA		6-6	34-61-11	D45247P	A19			D03261C	1			ALL
0311		22		PA		7-8	34-61-12	D03425	Q-			D45257P	B07			ALL
0312		22		PA		2-1	34-21-21	D45257P	A14			SM00044		W		ALL
0313		22		PA		1-9	34-21-21	D03693A	F14			GD05202	DC..	E	*3	ALL
0314		22		PA		1-7	34-21-21	D03693B	J05			GD05202	DC..	E	*3	ALL
0315		22		PA		1-7	34-21-21	D03693B	C04			GD05202	DC..	E	*3	YC051-YD153
0315		22		PA		1-7	34-21-21	D03693B	C04			GD05202	DC..	=		YD154-YR328
0319		22		PA		5-1	34-61-16	D03423	F			D41453J	1			ALL
0320		22		PA		2-4	34-61-16	D03427	F			SM00058		W		ALL
0321		22		PA		2-10	34-61-16	D03265	Y			SM00058		W		ALL
0322		22		PA		1-7	34-61-16	D03261B	K07			SM00058		W		ALL
0323		22		PA		3-5	34-61-16	D03261A	K13			D03265	X			ALL
0324		22		PA		3-5	34-61-18	D03261A	F09			D03265	A-			YC051-YC058
0325		22		PA		3-4	34-61-18	D03261B	A11			D03265	B-			YC051-YC058

WIRE LIST

D280A108

91-21-11

Section W0520

Page 34

Nov 12/2012



WIRE LIST

91-21-11

Section W0520

Page 35

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To							
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0523	286A0523			E5-2 SHELF WIRE BUNDLE #2 (continued)											
0366	20		PA		2-1	34-21-21	D45257P	A16			SM00051		W		ALL
0367	22		PA		4-7	34-21-21	D03693B	E11			SM00044		W		ALL
0368	22		PA		6-2	34-21-21	D45263P	A10			D03693B	K15			ALL
0369	22		PA		6-2	34-21-22	D03693A	J03			D45237P	B13			ALL
0370	22		PA		6-2	34-21-22	D03693A	J04			D45237P	B14			ALL
0373	22		PA		1-11	34-21-22	D45241P	B01			SM00051		W		ALL
0374	24		PK		2-7	34-61-26	D08105P	A05			D45067P	A01			YC059-YR328
0375	24		PK		9-4	34-61-26	D08105P	B07			D41453J	40			YC059-YR328
0377	24		PK		3-9	34-61-26	D41453J	39			TB0524Y	A015	1A		YC059-YR328
0378	22		G5		2-9	22-13-11	D45237P	B19			D45263P	A11			ALL
0379	22		G5		9-4	22-18-11	D45237P	B08			D41453J	2			ALL
0380	24		PK		2-10	31-62-25	D45237P	B07			D45247P	B08			ALL
0381	24		PK		2-10	31-62-25	D45237P	B01			D45247P	A03			ALL
0382	24		PK		2-10	31-62-25	D45237P	B02			D45247P	A02			ALL
0383	24		PK		2-10	31-62-25	D45237P	B03			D45247P	A01			ALL
0385	22		PA		9-4	34-51-41	D45237P	B06			D41453J	12			ALL
0386	22		PA		5-1	34-16-21	D03693A	F05			D41453J	13			ALL
0387	22		PA		6-2	34-16-21	D03693A	C09			D45237P	A20			ALL
0388	22		PA		2-1	34-21-16	D45257P	A08			SM00045		W		ALL
0390	24		PK		4-3	22-11-53	D41453J	41			TB0522Y	B007	1A		YC059-YR328
0391	24		PK		9-4	22-11-53	D45067P	A05			D41453J	44			YC059-YR328
0392	24		PK		9-4	22-11-53	D45067P	A06			D41453J	45			YC059-YR328
0393	24		PK		9-4	22-11-53	D45067P	A07			D41453J	46			YC059-YR328
2106B	22		PB	EF	1-11	34-21-21	D45237P	A05			SM00046		W		ALL
2106R	22		PB	EF	0-0	34-21-21	D45237P	A04			SM00045		W		ALL
2107B	22		PB	EG	2-9	27-32-21	D45241P	B03			D45263P	B17			ALL
2107R	22		PB	EG	0-0	27-32-21	D45241P	B02			D45263P	A17			ALL
2701B	24		Y2	AA	6-11	34-61-11	D08105P	A04			TB0524Y	B001	1A		ALL
2701R	24		Y2	AA	0-0	34-61-11	D08105P	A03			TB0524Y	A001	1A		ALL
2701Z				AA	0-0	34-61-11	D08105P	PERG	1F		GB00524	ST..	1A		ALL
2702B	24		Y2	AB	3-5	34-61-11	D03261A	E13			D03265	M			ALL
2702R	24		Y2	AB	0-0	34-61-11	D03261A	D13			D03265	L			ALL
2702Z				AB	0-0	34-61-11	GB00521	ST..	1A		D03265	DED			ALL
2703B	24		Y2	AC	3-5	34-61-11	D03261A	H13			D03265	P			ALL
2703R	24		Y2	AC	0-0	34-61-11	D03261A	G13			D03265	N			ALL
2703Z				AC	0-0	34-61-11	GB00521	ST..	1A		D03265	DED			ALL
2704B	24		Y2	AD	7-11	34-61-11	D08105P	A07			D03263	P			ALL
2704R	24		Y2	AD	0-0	34-61-11	D08105P	A06			D03263	N			ALL
2704Z				AD	0-0	34-61-11	D08105P	PERG	1F		D03263	DED			ALL

WIRE LIST

D280A108

91-21-11

Section W0520

Page 36

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0523		286A0523					E5-2 SHELF WIRE BUNDLE #2 (continued)									
2705B		24		Y2	AE	3-5	34-61-14	D03265		U		TB0524Y	B007	1A		ALL
2705R		24		Y2	AE	0-0	34-61-14	D03265		T		TB0524Y	A007	1A		ALL
2705Z					AE	0-0	34-61-14	D03265		DED		GB00524	ST..	1A		ALL
2706B		24		Y2	AF	3-5	34-61-14	D03265		F		TB0524Y	B005	1A		ALL
2706R		24		Y2	AF	0-0	34-61-14	D03265		E		TB0524Y	A005	1A		ALL
2706Z					AF	0-0	34-61-14	D03265		DED		GB00524	ST..	1A		ALL
2707B		24		Y2	AG	2-8	34-61-14	D03423		D		TB0521Y	B015	1A		ALL
2707R		24		Y2	AG	0-0	34-61-14	D03423		C		TB0521Y	A015	1A		ALL
2707Z					AG	0-0	34-61-14	D03423		DED		GB00521	ST..	1A		ALL
2708B		24		Y2	AH	7-6	34-61-14	D03423		B		D45263P	B12			ALL
2708R		24		Y2	AH	0-0	34-61-14	D03423		A		D45263P	A12			ALL
2708Z					AH	0-0	34-61-14	D03423		DED		D45263P	PERG	1F		ALL
2709B		24		Y2	AI	1-8	34-61-14	D03687B		A14		TB0524Y	B005	1A		ALL
2709R		24		Y2	AI	0-0	34-61-14	D03687B		A13		TB0524Y	A005	1A		ALL
2709Z					AI	0-0	34-61-14	D03687B		PERG	1A	GB00524	ST..	1A		ALL
2710B		24		Y2	AJ	3-0	34-61-14	D03427		D		TB0524Y	B007	1A		ALL
2710R		24		Y2	AJ	0-0	34-61-14	D03427		C		TB0524Y	A007	1A		ALL
2710Z					AJ	0-0	34-61-14	D03427		DED		GB00524	ST..	1A		ALL
2711B		24		Y2	AK	3-0	34-61-14	D03427		B		TB0524Y	B005	1A		ALL
2711R		24		Y2	AK	0-0	34-61-14	D03427		A		TB0524Y	A005	1A		ALL
2711Z					AK	0-0	34-61-14	D03427		DED		GB00524	ST..	1A		ALL
2712B		24		Y2	AL	6-3	34-61-14	D45263P		B04		TB0521Y	B015	1A		ALL
2712R		24		Y2	AL	0-0	34-61-14	D45263P		A04		TB0521Y	A015	1A		ALL
2712Z					AL	0-0	34-61-14	D45263P		PERG	1F	GB00521	ST..	1A		ALL
2713B		24		Y2	AM	6-4	34-61-14	D45247P		B10		TB0521Y	B015	1A		ALL
2713R		24		Y2	AM	0-0	34-61-14	D45247P		B09		TB0521Y	A015	1A		ALL
2713Z					AM	0-0	34-61-14	D45247P		PERG	1F	GB00521	ST..	1A		ALL
2714B		22		X2	AN	6-5	34-61-15	D45257P		B12		TB0522Y	B001	1A		ALL
2714R		22		X2	AN	0-0	34-61-15	D45257P		B11		TB0522Y	A001	1A		ALL
2714Z					AN	0-0	34-61-15	D45257P		PERG	1F	GB00522	ST..	1A		ALL
2715B		22		X2	AP	3-0	34-61-15	D03265		S		TB0522Y	B001	1A		ALL
2715R		22		X2	AP	0-0	34-61-15	D03265		R		TB0522Y	A001	1A		ALL
2715Z					AP	0-0	34-61-15	D03265		DED		GB00522	ST..	1A		ALL
2716B		22		N2	AQ	6-7	34-61-15	D03261B		H09		D45257P	B14			YC051-YC055
2716B		22		X2	AQ	1-8	34-61-15	D03261B		H09		TB0521Y	B009	1A		YC056-YR328
2716R		22		N2	AQ	0-0	34-61-15	D03261B		G09		D45257P	B13			YC051-YC055
2716R		22		X2	AQ	0-0	34-61-15	D03261B		G09		TB0521Y	A009	1A		YC056-YD157, YN501-YR328 YD158-YN260
2716R		22		X2	AQ	0-0	34-61-15	TB0521Y		A009	1A	D03261B	G09			

WIRE LIST

D280A108

91-21-11

Section W0520

Page 37

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0523	286A0523			E5-2 SHELF WIRE BUNDLE #2 (continued)											
2716Z				AQ	0-0	34-61-15	GB00521	ST..	1A		D45257P	PERG	1F		YC051-YC055
2716Z				AQ	0-0	34-61-15	GB00521	ST..	1A		TB0521Y	DED			YC056-YD157, YN501-YR328
2716Z				AQ	0-0	34-61-15	TB0521Y	DED			GB00521	ST..	1A		YD158-YN260
2717B	22	X2		AR	3-5	34-61-18	D03261A	H11			D03265	K			YC051-YC058
2717B	24	Y2		AR	6-6	34-61-18	D03261A	H11			D45067P	B03			YC059-YR328
2717R	22	X2		AR	0-0	34-61-18	D03261A	G11			D03265	J			YC051-YC058
2717R	24	Y2		AR	0-0	34-61-18	D03261A	G11			D45067P	A03			YC059-YR328
2717Z				AR	0-0	34-61-18	GB00521	ST..	1A		D03265	DED			YC051-YC058
2717Z				AR	0-0	34-61-18	GB00521	ST..	1A		D45067P	PERG	1F		YC059-YR328
2718B	24	Y2		AS	2-6	34-61-14	D03693B	A14			TB0524Y	B007	1A		ALL
2718R	24	Y2		AS	0-0	34-61-14	D03693B	A13			TB0524Y	A007	1A		ALL
2718Z				AS	0-0	34-61-14	D03693B	PERG	1A		GB00524	ST..	1A		ALL
2719B	24	Y2		AT	4-2	34-61-23	D45213P	B10			SM00202		W		YC051-YD157
2719B	24	Y2		AT	2-7	34-61-23	D45213P	B10			D08105P	B02			YD158-YR328
2719R	24	Y2		AT	0-0	34-61-23	D45213P	A10			SM00201		W		YC051-YD157
2719R	24	Y2		AT	0-0	34-61-23	D45213P	A10			D08105P	B01			YD158-YR328
2719Z				AT	0-0	34-61-23	D45213P	PERG	1F		SM00203		W		YC051-YD157
2719Z				AT	0-0	34-61-23	D45213P	PERG	1F		D08105P	PERG	1F		YD158-YR328
2720B	24	Y2		AU	6-0	34-21-21	D03693B	C06			D45237P	A03			ALL
2720R	24	Y2		AU	0-0	34-21-21	D03693B	C05			D45237P	A02			ALL
2720Z				AU	0-0	34-21-21	D03693B	PERG	1A		D45237P	PERG	1F		ALL
2721B	24	Y2		AV	6-1	34-21-22	D03693A	E10			D45241P	A02			ALL
2721R	24	Y2		AV	0-0	34-21-22	D03693A	D10			D45241P	A01			ALL
2721Z				AV	0-0	34-21-22	D03693A	PERG	1A		D45241P	PERG	1F		ALL
2722B	24	Y2		AW	6-4	34-21-22	D45247P	A13			D03693A	E09			ALL
2722R	24	Y2		AW	0-0	34-21-22	D45247P	A12			D03693A	D09			ALL
2722Z				AW	0-0	34-21-22	D45247P	PERG	1F		D03693A	PERG	1A		ALL
2723B	24	Y2		AX	5-1	34-21-22	D03693A	J08			D45239P	B03			YC051-YC060
2723R	24	Y2		AX	0-0	34-21-22	D03693A	H08			D45239P	B02			YC051-YC060
2723Z				AX	0-0	34-21-22	D03693A	PERG	1A		D45239P	PERG	1F		YC051-YC060
2724B	24	Y2		AY	6-2	34-21-23	D45237P	B10			TB0521Z	B017	1A		ALL
2724R	24	Y2		AY	0-0	34-21-23	D45237P	B09			TB0521Z	A017	1A		ALL
2724Z				AY	0-0	34-21-23	D45237P	PERG	1F		GB00521	ST..	1A		ALL
2725B	24	Y2		AZ	6-2	34-21-23	D45241P	B08			TB0521Z	B017	1A		YC051-YC052
2725R	24	Y2		AZ	0-0	34-21-23	D45241P	B07			TB0521Z	A017	1A		YC051-YC052
2725Z				AZ	0-0	34-21-23	D45241P	PERG	1F		GB00521	ST..	1A		YC051-YC052
2726B	24	Y2		BA	1-9	34-21-23	TB0521Z	B017	1A		D03693B	C11			ALL
2726R	24	Y2		BA	0-0	34-21-23	TB0521Z	A017	1A		D03693B	C10			ALL

WIRE LIST

D280A108

91-21-11

Section W0520

Page 38

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0523		286A0523			E5-2 SHELF WIRE BUNDLE #2 (continued)											
2726Z					BA	0-0	34-21-23	GB00521	ST..	1A		D03693B	PERG	1A		ALL
2727B	24	Y2			BB	6-4	34-21-23	D45263P	B16			TB0521Z	B017	1A		ALL
2727R	24	Y2			BB	0-0	34-21-23	D45263P	A16			TB0521Z	A017	1A		ALL
2727Z					BB	0-0	34-21-23	D45263P	PERG	1F		GB00521	ST..	1A		ALL
2728B	24	Y2			BC	6-3	34-21-23	D45263P	B15			TB0521Y	B013	1A		ALL
2728R	24	Y2			BC	0-0	34-21-23	D45263P	A15			TB0521Y	A013	1A		ALL
2728Z					BC	0-0	34-21-23	D45263P	PERG	1F		GB00521	ST..	1A		ALL
2729B	24	Y2			BD	1-8	34-21-23	TB0521Y	B013	1A		D03693B	E06			ALL
2729R	24	Y2			BD	0-0	34-21-23	TB0521Y	A013	1A		D03693B	E05			ALL
2729Z					BD	0-0	34-21-23	GB00521	ST..	1A		D03693B	PERG	1A		YC051-YD158, YL951-YR328
2730B	24	Y2			BE	4-8	34-21-23	D41453J	15			TB0521Y	B013	1A		ALL
2730R	24	Y2			BE	0-0	34-21-23	D41453J	14			TB0521Y	A013	1A		ALL
2730Z					BE	0-0	34-21-23	D41453J	S/R			GB00521	ST..	1A		ALL
2731B	24	Y2			BF	1-9	34-21-23	D03693B	K12			D03693A	E06			ALL
2731R	24	Y2			BF	0-0	34-21-23	D03693B	K11			D03693A	D06			ALL
2731Z					BF	0-0	34-21-23	D03693B	DED			D03693A	DED			ALL
2732B	24	Y2			BG	6-4	34-21-23	D45257P	B04			TB0521Z	B017	1A		ALL
2732R	24	Y2			BG	0-0	34-21-23	D45257P	B03			TB0521Z	A017	1A		ALL
2732Z					BG	0-0	34-21-23	D45257P	PERG	1F		GB00521	ST..	1A		ALL
2733B	24	Y2			BH	6-3	34-21-23	D45257P	B06			TB0521Y	B011	1A		ALL
2733R	24	Y2			BH	0-0	34-21-23	D45257P	B05			TB0521Y	A011	1A		ALL
2733Z					BH	0-0	34-21-23	D45257P	PERG	1F		GB00521	ST..	1A		ALL
2734B	24	Y2			BI	1-8	34-21-23	TB0521Y	B011	1A		D03693B	G08			ALL
2734R	24	Y2			BI	0-0	34-21-23	TB0521Y	A011	1A		D03693B	G07			ALL
2734Z					BI	0-0	34-21-23	GB00521	ST..	1A		D03693B	PERG	1A		ALL
2735B	24	Y2			BJ	4-7	34-21-23	D41453J	19			TB0521Y	B011	1A		ALL
2735R	24	Y2			BJ	0-0	34-21-23	D41453J	18			TB0521Y	A011	1A		ALL
2735Z					BJ	0-0	34-21-23	D41453J	S/R			GB00521	ST..	1A		ALL
2736B	24	Y2			BK	6-4	34-21-23	D45257P	B02			TB0521Z	B017	1A		ALL
2736R	24	Y2			BK	0-0	34-21-23	D45257P	B01			TB0521Z	A017	1A		ALL
2736Z					BK	0-0	34-21-23	D45257P	PERG	1F		GB00521	ST..	1A		ALL
2737B	24	Y2			BL	2-5	34-21-23	TB0521Z	B017	1A		D02179B	B03			ALL
2737R	24	Y2			BL	0-0	34-21-23	TB0521Z	A017	1A		D02179B	A03			ALL
2737Z					BL	0-0	34-21-23	GB00521	ST..	1A		D02179B	DED			ALL
2738B	24	Y2			BM	2-7	23-27-13	D08105P	B04			D45211P	B07			YC051-YD157
2738B	24	Y2			BM	3-1	23-27-33	D08105P	B04			SM00066		W		YD158-YN260
2738B	24	Y2			BM	2-7	23-27-33	D08105P	B04			D45213P	B14			YN501-YR328
2738R	24	Y2			BM	0-0	23-27-13	D08105P	B03			D45211P	A07			YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0520

Page 39

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0523	286A0523			E5-2 SHELF WIRE BUNDLE #2 (continued)											
2738R	24	Y2	BM		0-0	23-27-33	D08105P	B03			SM00065		W		YD158-YN260
2738R	24	Y2	BM		0-0	23-27-33	D08105P	B03			D45213P	A14			YN501-YR328
2738Z			BM		0-0	23-27-13	D08105P	PERG	1F		D45211P	PERG	1F		YC051-YD157
2738Z			BM		0-0	23-27-33	D08105P	PERG	1F		SM00067		W		YD158-YN260
2738Z			BM		0-0	23-27-33	D08105P	PERG	1F		D45213P	PERG	1F		YN501-YR328
2739B	24	Y2	BN		6-3	34-21-24	D45247P	B05			TB0521Z	B005	1A		ALL
2739R	24	Y2	BN		0-0	34-21-24	D45247P	B04			TB0521Z	A005	1A		ALL
2739Z			BN		0-0	34-21-24	D45247P	PERG	1F		GB00521	ST..	1A		ALL
2740B	24	Y2	BP		1-11	34-21-24	TB0521Z	B021	1A		D03693B	K05			ALL
2740R	24	Y2	BP		0-0	34-21-24	TB0521Z	A021	1A		D03693B	K04			ALL
2740Z			BP		0-0	34-21-24	GB00521	ST..	1A		D03693B	PERG	1A		ALL
2741B	24	Y2	BQ		5-1	34-21-24	D41453J	17			D03693A	B03			ALL
2741R	24	Y2	BQ		0-0	34-21-24	D41453J	16			D03693A	A03			ALL
2741Z			BQ		0-0	34-21-24	D41453J	S/R			D03693A	PERG	1A		ALL
2742B	24	Y2	BR		6-5	34-21-24	D45263P	B09			TB0521Z	B021	1A		ALL
2742R	24	Y2	BR		0-0	34-21-24	D45263P	A09			TB0521Z	A021	1A		ALL
2742Z			BR		0-0	34-21-24	D45263P	PERG	1F		GB00521	ST..	1A		ALL
2743B	24	Y2	BS		2-0	34-21-24	TB0521Z	B021	1A		D03693A	B09			ALL
2743R	24	Y2	BS		0-0	34-21-24	TB0521Z	A021	1A		D03693A	A09			ALL
2743Z			BS		0-0	34-21-24	GB00521	ST..	1A		D03693A	PERG	1A		ALL
2744B	24	Y2	BT		6-4	34-21-24	D45247P	B07			D03693A	B07			ALL
2744R	24	Y2	BT		0-0	34-21-24	D45247P	B06			D03693A	A07			ALL
2744Z			BT		0-0	34-21-24	D45247P	PERG	1F		D03693A	PERG	1A		ALL
2745B	24	Y2	BU		6-6	34-21-24	D45257P	A04			TB0521Z	B021	1A		ALL
2745R	24	Y2	BU		0-0	34-21-24	D45257P	A03			TB0521Z	A021	1A		ALL
2745Z			BU		0-0	34-21-24	D45257P	PERG	1F		GB00521	ST..	1A		ALL
2746B	24	Y2	BV		6-4	34-21-24	D45257P	A06			D03693A	B05			ALL
2746R	24	Y2	BV		0-0	34-21-24	D45257P	A05			D03693A	A05			ALL
2746Z			BV		0-0	34-21-24	D45257P	PERG	1F		D03693A	PERG	1A		ALL
2747B	24	Y2	BW		6-2	34-21-24	D45263P	B06			TB0521Z	B005	1A		YC051-YD157
2747B	24	Y2	BW		6-3	34-21-24	D45247P	B20			TB0521Z	B005	1A		YD158-YR328
2747R	24	Y2	BW		0-0	34-21-24	D45263P	A06			TB0521Z	A005	1A		YC051-YD157
2747R	24	Y2	BW		0-0	34-21-24	D45247P	B19			TB0521Z	A005	1A		YD158-YR328
2747Z			BW		0-0	34-21-24	D45263P	PERG	1F		GB00521	ST..	1A		YC051-YD157
2747Z			BW		0-0	34-21-24	D45247P	PERG	1F		GB00521	ST..	1A		YD158-YR328
2749B	24	Y2	BY		2-4	34-21-24	TB0521Z	B005	1A		D02179B	E05			ALL
2749R	24	Y2	BY		0-0	34-21-24	TB0521Z	A005	1A		D02179B	D05			ALL
2749Z			BY		0-0	34-21-24	GB00521	ST..	1A		D02179B	DED			ALL
2750B	24	Y2	BZ		2-9	31-35-02	D45263P	B02			D08105P	B06			ALL

WIRE LIST

D280A108

91-21-11

Section W0520

Page 40

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0523		286A0523					E5-2 SHELF WIRE BUNDLE #2 (continued)									
2750R		24		Y2	BZ	0-0	31-35-02	D45263P	B01			D08105P	B05			ALL
2750Z					BZ	0-0	31-35-02	D45263P	PERG	1F		D08105P	PERG	1F		ALL
2754B		24		Y2	CD	2-10	31-62-25	D45237P	B12			D45257P	B16			ALL
2754R		24		Y2	CD	0-0	31-62-25	D45237P	B11			D45257P	B15			ALL
2754Z					CD	0-0	31-62-25	D45237P	PERG	1F		D45257P	PERG	1F		ALL
2755B		24		Y2	CE	7-4	31-62-25	D45257P	B18			D02179A	H03			ALL
2755R		24		Y2	CE	0-0	31-62-25	D45257P	B17			D02179A	G03			ALL
2755Z					CE	0-0	31-62-25	D45257P	PERG	1F		GB00523	ST..	1A		ALL
2756B		24		Y2	CF	6-8	31-62-25	D45257P	B20			D03261A	H03			ALL
2756R		24		Y2	CF	0-0	31-62-25	D45257P	B19			D03261A	G03			ALL
2756Z					CF	0-0	31-62-25	D45257P	PERG	1F		GB00521	ST..	1A		ALL
2757B		24		Y2	CG	7-8	31-62-25	D45247P	A05			D03687A	G13			ALL
2757R		24		Y2	CG	0-0	31-62-25	D45247P	A04			D03687A	F13			ALL
2757Z					CG	0-0	31-62-25	D45247P	PERG	1F		D03687A	PERG	1A		ALL
2758B		24		Y2	CH	6-4	31-62-25	D45247P	A07			D03693A	G15			ALL
2758R		24		Y2	CH	0-0	31-62-25	D45247P	A06			D03693A	F15			ALL
2758Z					CH	0-0	31-62-25	D45247P	PERG	1F		D03693A	PERG	1A		ALL
2759B		24		Y2	CI	4-0	34-31-21	D41453J	4			D02179B	H05			ALL
2759R		24		Y2	CI	0-0	34-31-21	D41453J	3			D02179B	G05			ALL
2759Z					CI	0-0	34-31-21	D41453J	S/R			GB00524	ST..	1A		ALL
2760B		24		Y2	CJ	4-7	34-31-21	D41453J	6			D03261B	H05			ALL
2760R		24		Y2	CJ	0-0	34-31-21	D41453J	5			D03261B	G05			ALL
2760Z					CJ	0-0	34-31-21	D41453J	S/R			GB00521	ST..	1A		ALL
2761B		24		Y2	CK	4-0	34-51-21	D41453J	8			D02179B	E01			ALL
2761R		24		Y2	CK	0-0	34-51-21	D41453J	7			D02179B	D01			ALL
2761Z					CK	0-0	34-51-21	D41453J	S/R			GB00524	ST..	1A		ALL
2762B		24		Y2	CL	4-7	34-51-21	D41453J	10			D03261B	E01			ALL
2762R		24		Y2	CL	0-0	34-51-21	D41453J	9			D03261B	D01			ALL
2762Z					CL	0-0	34-51-21	D41453J	S/R			GB00522	ST..	1A		ALL
2764B		24		Y2	CN	2-0	34-55-21	D02179B	H07			TB0522Y	B003	1A		ALL
2764R		24		Y2	CN	0-0	34-55-21	D02179B	G07			TB0522Y	A003	1A		ALL
2764Z					CN	0-0	34-55-21	GB00523	ST..	1A		GB00522	ST..	1A		ALL
2765B		24		Y2	CP	6-6	34-55-21	D45247P	A15			TB0522Y	B003	1A		ALL
2765R		24		Y2	CP	0-0	34-55-21	D45247P	A14			TB0522Y	A003	1A		ALL
2765Z					CP	0-0	34-55-21	D45247P	PERG	1F		GB00522	ST..	1A		ALL
2766B		24		Y2	CQ	1-8	34-61-11	D02179A	E11			TB0524Y	B001	1A		ALL
2766R		24		Y2	CQ	0-0	34-61-11	D02179A	D11			TB0524Y	A001	1A		ALL
2766Z					CQ	0-0	34-61-11	D02179A	DED			GB00524	ST..	1A		ALL
2767B		24		Y2	CR	2-4	34-61-11	D03261A	E11			TB0524Y	B001	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0520

Page 41

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0523	286A0523			E5-2 SHELF WIRE BUNDLE #2 (continued)											
2767R	24	Y2	CR		0-0	34-61-11	D03261A	D11			TB0524Y	A001	1A		ALL
2767Z			CR		0-0	34-61-11	D03261A	DED			GB00524	ST..	1A		ALL
2768B	24	Y2	CS		2-3	34-61-14	D03261B	E07			TB0524Y	B007	1A		ALL
2768R	24	Y2	CS		0-0	34-61-14	D03261B	D07			TB0524Y	A007	1A		ALL
2768Z			CS		0-0	34-61-14	D03261B	DED			GB00524	ST..	1A		ALL
2769B	24	Y2	CT		2-4	34-61-14	D03261A	H09			TB0524Y	B005	1A		ALL
2769R	24	Y2	CT		0-0	34-61-14	D03261A	G09			TB0524Y	A005	1A		ALL
2769Z			CT		0-0	34-61-14	D03261A	DED			GB00524	ST..	1A		ALL
2770B	22	X2	CU		1-8	34-61-15	D03261A	B11			TB0522Y	B001	1A		ALL
2770R	22	X2	CU		0-0	34-61-15	D03261A	A11			TB0522Y	A001	1A		ALL
2770Z			CU		0-0	34-61-15	D03261A	DED			GB00522	ST..	1A		ALL
2771B	24	Y2	CV		1-7	34-55-21	D03261B	H07			TB0522Y	B003	1A		ALL
2771R	24	Y2	CV		0-0	34-55-21	D03261B	G07			TB0522Y	A003	1A		ALL
2771Z			CV		0-0	34-55-21	D03261B	DED			GB00522	ST..	1A		ALL
2772B	24	Y2	CW		1-9	34-21-23	TB0521Z	B017	1A		D03261B	B03			ALL
2772R	24	Y2	CW		0-0	34-21-23	TB0521Z	A017	1A		D03261B	A03			ALL
2772Z			CW		0-0	34-21-23	D03261B	DED			GB00521	ST..	1A		ALL
2776B	24	Y2	DA		6-0	34-21-24	D45241P	A07			TB0521Z	B005	1A		YC051-YC052
2776B	24	Y2	DA		6-3	34-21-24	D45247P	B18			TB0521Z	B005	1A		YC053-YR328
2776R	24	Y2	DA		0-0	34-21-24	D45241P	A06			TB0521Z	A005	1A		YC051-YC052
2776R	24	Y2	DA		0-0	34-21-24	D45247P	B17			TB0521Z	A005	1A		YC053-YR328
2776Z			DA		0-0	34-21-24	D45241P	PERG	1F		GB00521	ST..	1A		YC051-YC052
2776Z			DA		0-0	34-21-24	D45247P	PERG	1F		GB00521	ST..	1A		YC053-YR328
2779B	24	Y2	DD		2-4	34-58-11	D03693B	J03			SM00002		W		YC051-YD158
2779R	24	Y2	DD		0-0	34-58-11	D03693B	J02			SM00001		W		YC051-YD158
2779Z			DD		0-0	34-58-11	D03693B	PERG	1A		SM00003		W		YC051-YD158
2780B	24	Y2	DE		6-0	34-58-11	D41251J	32			SM00002		W		YC051-YD158
2780R	24	Y2	DE		0-0	34-58-11	D41251J	31			SM00001		W		YC051-YD158
2780Z			DE		0-0	34-58-11	D41251J	S/R			SM00003		W		YC051-YD158
2783B	24	Y2	DH		4-7	34-58-21	D41453J	26			SM00063		W		ALL
2783R	24	Y2	DH		0-0	34-58-21	D41453J	25			SM00062		W		ALL
2783Z			DH		0-0	34-58-21	D41453J	S/R			SM00064		W		ALL
2784B	24	Y2	DI		6-2	34-58-21	D41453J	28			SM00002		W		YC051-YD158
2784B	24	Y2	DI		4-8	34-58-21	D41453J	28			TB0521Y	B013	1A		YL951-YR328
2784R	24	Y2	DI		0-0	34-58-21	D41453J	27			SM00001		W		YC051-YD158
2784R	24	Y2	DI		0-0	34-58-21	D41453J	27			TB0521Y	A013	1A		YL951-YR328
2784Z			DI		0-0	34-58-21	D41453J	S/R			SM00003		W		YC051-YD158
2784Z			DI		0-0	34-58-21	D41453J	S/R			GB00521	ST..	1A		YL951-YR328
2786B	24	Y2	DK		3-6	34-61-14	D03263	U			TB0524Y	B023	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W0520

Page 42

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W0523	286A0523				E5-2 SHELF WIRE BUNDLE #2 (continued)											
2786R	24	Y2	DK		0-0	34-61-14	D03263		T		TB0524Y	A023	1A		ALL	
2786Z			DK		0-0	34-61-14	D03263		DED		GB00524	ST..	1A		ALL	
2787B	24	Y2	DL		4-0	34-58-21	D41453J		30		D02179B	H01			ALL	
2787R	24	Y2	DL		0-0	34-58-21	D41453J		29		D02179B	G01			ALL	
2787Z			DL		0-0	34-58-21	D41453J		S/R		GB00524	ST..	1A		ALL	
2788B	24	Y2	DM		0-7	34-58-21	D03261B		H01		SM00063		W		ALL	
2788R	24	Y2	DM		0-0	34-58-21	D03261B		G01		SM00062		W		ALL	
2788Z			DM		0-0	34-58-21	D03261B		DED		SM00064		W		ALL	
2789B	24	Y2	DN		6-5	34-58-21	D45237P		B16		SM00063		W		ALL	
2789R	24	Y2	DN		0-0	34-58-21	D45237P		B15		SM00062		W		ALL	
2789Z			DN		0-0	34-58-21	D45237P		PERG	1F	SM00064		W		ALL	
2790B	24	Y2	DP		4-2	34-58-21	D45237P		B18		SM00002		W		YC051-YD158	
2790B	24	Y2	DP		9-4	34-31-21	D45237P		B18		D41453J	55			YL951-YR328	
2790R	24	Y2	DP		0-0	34-58-21	D45237P		B17		SM00001		W		YC051-YD158	
2790R	24	Y2	DP		0-0	34-31-21	D45237P		B17		D41453J	53			YL951-YR328	
2790Z			DP		0-0	34-58-21	D45237P		PERG	1F	SM00003		W		YC051-YD158	
2790Z			DP		0-0	34-31-21	D45237P		PERG	1F	D41453J	S/R			YL951-YR328	
2793B	24	Y2	DS		1-7	34-21-24	TB0521Z		B005	1A	TB0521Z	B021	1A		ALL	
2793R	24	Y2	DS		0-0	34-21-24	TB0521Z		A005	1A	TB0521Z	A021	1A		ALL	
2793Z			DS		0-0	34-21-24	TB0521Z		DED		TB0521Z	DED			ALL	
2794B	24	Y2	DT		1-8	34-21-24	TB0521Z		B005	1A	D03261B	E05			ALL	
2794R	24	Y2	DT		0-0	34-21-24	TB0521Z		A005	1A	D03261B	D05			ALL	
2794Z			DT		0-0	34-21-24	D03261B		DED		GB00521	ST..	1A		ALL	
2795B	24	Y2	DU		7-5	34-61-14	D45247P		B12		TB0524Y	B023	1A		ALL	
2795R	24	Y2	DU		0-0	34-61-14	D45247P		B11		TB0524Y	A023	1A		ALL	
2795Z			DU		0-0	34-61-14	D45247P		PERG	1F	GB00524	ST..	1A		ALL	
2796B	24	Y2	DV		7-2	34-61-21	D45213P		B09		TB0524Y	B023	1A		ALL	
2796R	24	Y2	DV		0-0	34-61-21	D45213P		A09		TB0524Y	A023	1A		ALL	
2796Z			DV		0-0	34-61-21	D45213P		PERG	1F	GB00524	ST..	1A		ALL	
2797B	24	Y2	DW		6-3	34-61-14	D45257P		A10		TB0521Y	B015	1A		YD158-YD170	
2797R	24	Y2	DW		0-0	34-61-14	D45257P		A09		TB0521Y	A015	1A		YD158-YD170	
2797Z			DW		0-0	34-61-14	D45257P		PERG	1F	GB00521	ST..	1A		YD158-YD170	
2798B	24	Y2	BX		6-3	34-61-15	D45257P		B14		TB0521Y	B009	1A		YC056-YD157	
2798B	24	Y2	DX		6-3	34-61-15	D45257P		B14		TB0521Y	B009	1A		YD158-YR328	
2798R	24	Y2	BX		0-0	34-61-15	D45257P		B13		TB0521Y	A009	1A		YC056-YD157	
2798R	24	Y2	DX		0-0	34-61-15	D45257P		B13		TB0521Y	A009	1A		YD158-YR328	
2798Z			BX		0-0	34-61-15	D45257P		PERG	1F	GB00521	ST..	1A		YC056-YD157	
2798Z			DX		0-0	34-61-15	D45257P		PERG	1F	GB00521	ST..	1A		YD158-YR328	

WIRE LIST

D280A108

91-21-11

Section W0520

Page 43

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From				To						
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0523	286A0523			E5-2 SHELF WIRE BUNDLE #2 (continued)											
2799B	24	Y2	DY		2-11	34-61-15	D03427	K			TB0521Y	B009	1A		YC056-YD170, YN501-YR328
2799B	24	Y2	DY		2-11	34-61-15	D03427	K			TB0521Y	B009	%A		YL951-YN260
2799R	24	Y2	DY		0-0	34-61-15	D03427	J			TB0521Y	A009	1A		YC056-YD170, YN501-YR328
2799R	24	Y2	DY		0-0	34-61-15	D03427	J			TB0521Y	A009	%A		YL951-YN260
2799Z			DY		0-0	34-61-15	D03427	DED			GB00521	ST..	1A		YC056-YR328
2801B	24	Y2	IA		7-5	34-61-15	D45257P	A12			TB0524Y	B021	1A		YD158-YD170
2801R	24	Y2	IA		0-0	34-61-15	D45257P	A11			TB0524Y	A021	1A		YD158-YD170
2801Z			IA		0-0	34-61-15	D45257P	PERG	1F		TB0524Y	DED			YD158-YD170
2802B	24	Y2	IB		3-4	34-61-21	D03265	W			D03261B	B09			ALL
2802R	24	Y2	IB		0-0	34-61-21	D03265	V			D03261B	A09			ALL
2802Z			IB		0-0	34-61-21	D03265	DED			GB00521	ST..	1A		ALL
2803B	24	Y2	IC		3-4	34-61-21	D03265	B			D03261B	H03			ALL
2803R	24	Y2	IC		0-0	34-61-21	D03265	A			D03261B	G03			ALL
2803Z			IC		0-0	34-61-21	D03265	DED			GB00521	ST..	1A		ALL
2804B	24	Y6	ID		3-10	34-61-15	D41453J	34			TB0523Y	B009	1A		YC051-YD157
2804B	24	Y2	ID		3-8	34-61-15	D41453J	34			TB0524Y	B003	1A		YD158-YD170
2804R	24	Y6	ID		0-0	34-61-15	D41453J	33			TB0523Y	A009	1A		YC051-YD157
2804R	24	Y2	ID		0-0	34-61-15	D41453J	33			TB0524Y	A003	1A		YD158-YD170
2804Z			ID		0-0	34-61-15	D41453J	S/R			GB00523	ST..	1A		YC051-YD157
2804Z			ID		0-0	34-61-15	D41453J	S/R			GB00524	ST..	1A		YD158-YD170
2805B	24	Y2	IE		3-1	23-27-33	D45213P	B14			SM00066		W		YD158-YN260
2805R	24	Y2	IE		0-0	23-27-33	D45213P	A14			SM00065		W		YD158-YN260
2805Z			IE		0-0	23-27-33	D45213P	PERG	1F		SM00067		W		YD158-YN260
2806B	24	Y2	IF		4-6	34-61-23	D45001P	B11			SM00202		W		YC051-YD157
2806R	24	Y2	IF		0-0	34-61-23	D45001P	A11			SM00201		W		YC051-YD157
2806Z			IF		0-0	34-61-23	D45001P	PERG	1F		SM00203		W		YC051-YD157
2807B	24	Y2	IG		6-4	23-27-33	D45213P	B15			D03261B	CAP	Y		YD158-YN260
2807R	24	Y2	IG		0-0	23-27-33	D45213P	A15			D03261B	CAP	Y		YD158-YN260
2807Z			IG		0-0	23-27-33	D45213P	PERG	1F		D03261B	DED			YD158-YN260
2812B	24	Y2	IL		3-10	23-27-33	D03261B	CAP	Y		SM00066		W		YD158-YN260
2812R	24	Y2	IL		0-0	23-27-33	D03261B	CAP	Y		SM00065		W		YD158-YN260
2812Z			IL		0-0	23-27-33	D03261B	DED			SM00067		W		YD158-YN260
2814B	24	Y2	IN		6-4	34-61-25	D03261B	CAP	Y		D45213P	B03			YD158-YN260
2814R	24	Y2	IN		0-0	34-61-25	D03261B	CAP	Y		D45213P	A03			YD158-YN260
2814Z			IN		0-0	34-61-25	D03261B	DED			D45213P	PERG	1F		YD158-YN260
2815B	24	Y2	IP		6-4	34-61-25	D03261B	CAP	Y		D45213P	B04			YD158-YN260
2815R	24	Y2	IP		0-0	34-61-25	D03261B	CAP	Y		D45213P	A04			YD158-YN260

WIRE LIST

D280A108

91-21-11

Section W0520

Page 44

Nov 12/2012

Bundle No. Wire No.	Part Number			Description Fam	FT-IN	Diagram	From				To					
	GA	CO	TY				Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W0523	286A0523			E5-2 SHELF WIRE BUNDLE #2 (continued)												
2815Z				IP	0-0	34-61-25	D03261B	DED				D45213P	PERG	1F		YD158-YN260
2816B	24	Y2		IQ	6-4	34-61-25	D03261B	CAP	Y			D45213P	B05			YD158-YN260
2816R	24	Y2		IQ	0-0	34-61-25	D03261B	CAP	Y			D45213P	A05			YD158-YN260
2816Z				IQ	0-0	34-61-25	D03261B	DED				D45213P	PERG	1F		YD158-YN260
2817B	24	Y2		IR	6-6	34-61-24	D03261B	H02				D45263P	B03			YC051-YD157
2817B	24	Y2		IR	6-6	34-61-24	D45263P	B03				D03261B	H02			YD158-YR328
2817R	24	Y2		IR	0-0	34-61-24	D03261B	G02				D45263P	A03			YC051-YD157
2817R	24	Y2		IR	0-0	34-61-24	D45263P	A03				D03261B	G02			YD158-YR328
2817Z				IR	0-0	34-61-24	GB00521	ST..	1A			D45263P	PERG	1F		YC051-YD157
2817Z				IR	0-0	34-61-24	D45263P	PERG	1F			D03261B	DED			YD158-YR328
2818B	24	Y2		IS	6-6	31-33-01	D03261B	B08				D45263P	B13			ALL
2818R	24	Y2		IS	0-0	31-33-01	D03261B	A08				D45263P	A13			ALL
2818Z				IS	0-0	31-33-01	GB00521	ST..	1A			D45263P	PERG	1F		ALL
2819B	24	Y2		IT	4-2	34-61-23	D08105P	B02				SM00202		W		YC051-YD157
2819R	24	Y2		IT	0-0	34-61-23	D08105P	B01				SM00201		W		YC051-YD157
2819Z				IT	0-0	34-61-23	D08105P	PERG	1F			SM00203		W		YC051-YD157
2820B	24	Y2		EU	6-6	34-21-24	D45247P	B16				TB0521Z	B021	1A		YC053-YR328
2820R	24	Y2		EU	0-0	34-21-24	D45247P	B15				TB0521Z	A021	1A		YC053-YR328
2820Z				EU	0-0	34-21-24	D45247P	PERG	1F			GB00521	ST..	1A		YC053-YR328
2828B	22	X2		JC	6-7	31-32-15	D45237P	A19				TB0522Y	B021	1A		YC059-YR328
2828R	22	X2		JC	0-0	31-32-15	D45237P	A15				TB0522Y	A021	1A		YC059-YR328
2828Z				JC	0-0	31-32-15	D45237P	PERG	1F			GB00522	ST..	1A		YC059-YR328
2829B	22	X2		JD	4-6	31-32-15	D41453J	38				TB0522Y	B021	1A		YC059-YR328
2829R	22	X2		JD	0-0	31-32-15	D41453J	37				TB0522Y	A021	1A		YC059-YR328
2829Z				JD	0-0	31-32-15	D41453J	S/R				GB00522	ST..	1A		YC059-YR328
2831B	24	Y2		JF	1-11	34-61-18	D03261A	E09				TB0522Y	B021	1A		YC059-YR328
2831R	24	Y2		JF	0-0	34-61-18	D03261A	D09				TB0522Y	A021	1A		YC059-YR328
2831Z				JF	0-0	34-61-18	D03261A	DED				GB00522	ST..	1A		YC059-YR328
2832B	24	Y2		JG	6-11	34-61-26	D45067P	B02				TB0524Y	B001	1A		YC059-YR328
2832R	24	Y2		JG	0-0	34-61-26	D45067P	A02				TB0524Y	A001	1A		YC059-YR328
2832Z				JG	0-0	34-61-26	D45067P	PERG	1F			GB00524	ST..	1A		YC059-YR328
2833B	24	Y2		JH	6-7	34-61-26	D08105P	B11				TB0522Y	B021	1A		YC059-YR328
2833R	24	Y2		JH	0-0	34-61-26	D08105P	A11				TB0522Y	A021	1A		YC059-YR328
2833Z				JH	0-0	34-61-26	D08105P	PERG	1F			GB00522	ST..	1A		YC059-YR328
2834B	24	Y2		JI	9-4	22-11-53	D45067P	B04				D41453J	43			YC059-YR328
2834R	24	Y2		JI	0-0	22-11-53	D45067P	A04				D41453J	42			YC059-YR328
2834Z				JI	0-0	22-11-53	D45067P	PERG	1F			D41453J	S/R			YC059-YR328
2835B	24	Y2		JJ	3-0	34-61-15	D03423	K				TB0524Y	B021	1A		YD158-YD170
2835R	24	Y2		JJ	0-0	34-61-15	D03423	J				TB0524Y	A021	1A		YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0520

Page 45

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0523		286A0523			E5-2 SHELF WIRE BUNDLE #2 (continued)											
2835Z					JJ	0-0	34-61-15	D03423	DED			GB00524	ST..	1A		YD158-YD170
2839B		24		Y2	JN	6-3	34-21-23	D45247P	A18			TB0521Y	B011	1A		YD158-YR328
2839R		24		Y2	JN	0-0	34-21-23	D45247P	A17			TB0521Y	A011	1A		YD158-YR328
2839Z					JN	0-0	34-21-23	D45247P	PERG	1F		TB0521Y	DED			YD158-YD170
2839Z					JN	0-0	34-21-23	D45247P	PERG	1F		GB00521	ST..	1A		YL951-YR328
2841B		24		Y2	JQ	3-8	34-21-14	D03687A	B07			D41453J	52			YD157-YR328
2841R		24		Y2	JQ	0-0	34-21-14	D03687A	A07			D41453J	51			YD157-YR328
2841Z					JQ	0-0	34-21-14	D03687A	PERG	1A		D41453J	S/R			YD157-YR328
3101B		24		PM	GA	6-1	34-21-22	D03693A	H07			D45241P	A09			ALL
3101R		24		PM	GA	0-0	34-21-22	D03693A	J07			D45241P	A08			ALL
3101Y		24		PM	GA	0-0	34-21-22	D03693A	K07			D45241P	A10			ALL
3102B		22		PC	GB	2-9	27-32-21	D45241P	B05			D45263P	B19			ALL
3102R		22		PC	GB	0-0	27-32-21	D45241P	B04			D45263P	B18			ALL
3102Y		22		PC	GB	0-0	27-32-21	D45241P	B06			D45263P	B20			ALL
3601B		22		X3	HA	6-3	34-21-22	D45241P	A04			TB0522Y	B005	1A		ALL
3601R		22		X3	HA	0-0	34-21-22	D45241P	A03			TB0522Y	A005	1A		ALL
3601Y		22		X3	HA	0-0	34-21-22	D45241P	A05			TB0522Y	A007	1A		ALL
3601Z					HA	0-0	34-21-22	D45241P	PERG	1F		GB00522	ST..	1A		ALL
3602B		22		X3	HB	2-0	34-21-22	D03693A	H06			TB0522Y	B005	1A		ALL
3602R		22		X3	HB	0-0	34-21-22	D03693A	G06			TB0522Y	A005	1A		ALL
3602Y		22		X3	HB	0-0	34-21-22	D03693A	J06			TB0522Y	A007	1A		ALL
3602Z					HB	0-0	34-21-22	D03693A	PERG	1A		GB00522	ST..	1A		ALL
3603B		22		X3	HC	6-6	34-21-22	D45247P	A10			TB0522Y	B005	1A		ALL
3603R		22		X3	HC	0-0	34-21-22	D45247P	A09			TB0522Y	A005	1A		ALL
3603Y		22		X3	HC	0-0	34-21-22	D45247P	A11			TB0522Y	A007	1A		ALL
3603Z					HC	0-0	34-21-22	D45247P	PERG	1F		GB00522	ST..	1A		ALL

WIRE LIST

D280A108

91-21-11
Section W0520
Page 46 End
Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice
W0613	286A0613				E6-1 ELECTRONIC SHELF (SATCOM)										
0001	20		PA		2-6	23-15-11	D41613J		1	TB6101Z	A021	1A		YC051-YD157	
0002	20		PA		1-11	23-15-11	D10857C		1	TB6101Z	A021	1A		YC051-YD157	
0003	20		PA		1-6	23-15-11	D10857C		7	GD06102	AC..	1		YC051-YD157	
0004	20		PA		1-6	23-15-11	D10857C		8	GD06102	ST..	1		YC051-YD157	
0005	20		PA		2-5	23-15-11	D10859C		1	TB6101Z	A021	1A		YC051-YD157	
0006	20		PA		1-10	23-15-11	D10859C		7	GD06102	AC..	1		YC051-YD157	
0007	20		PA		1-10	23-15-11	D10859C		8	GD06102	ST..	1		YC051-YD157	
0008	20		PA		2-9	23-15-11	D10865		1	TB6101Z	A021	1A		YC051-YD157	
0009	20		PA		2-4	23-15-11	D10865		3	GD06102	AC..	1		YC051-YC057	
0009	20		PA		2-5	23-15-11	D10865		3	GD06102	AC..	1		YC058-YD157	
0010	20		PA		2-4	23-15-11	D10865		4	GD06102	ST..	1		YC051-YC057	
0010	20		PA		2-5	23-15-11	D10865		4	GD06102	ST..	1		YC058-YD157	
0011	24		PK		2-8	31-31-17	D06103J		6	TB6101Y	A025	1A		YC051-YD157	
0012	24		PK		2-8	31-31-17	D06103J		7	TB6101Y	B025	1A		YC051-YD157	
0013	24		PK		2-8	23-15-12	D06103J		8	TB6101Y	B025	1A		YC051-YD157	
0014	24		PK		2-8	23-15-12	D06103J		9	TB6101Y	A025	1A		YC051-YD157	
0015	24		PK		2-0	23-15-12	D10857B	F08		TB6101Y	B025	1A		YC051-YC057	
0015	24		PK		2-0	23-15-12	D10857B	H08		TB6101Y	B025	1A		YC058-YD157	
0016	24		PK		2-0	23-15-12	D10857B	H08		TB6101Y	A025	1A		YC051-YC057	
0016	24		PK		2-0	23-15-12	D10857B	F08		TB6101Y	A025	1A		YC058-YD157	
0017	22		PA		3-3	23-15-12	D10859B	K05		D41619J		1		YC051-YD157	
0018	22		PA		3-1	23-15-12	D10859C		9	D41619J		2		YC051-YD157	
0019	22		PA		3-1	23-15-12	D10859C		11	D41619J		3		YC051-YD157	
001CO				CA	0-0	23-15-12	D10859B	= C71		D41617J	= C1			YC051-YD157	
001CX			JB	CA	2-1	23-15-12	D10859B	71	5A	D41617J	= A1			YC051-YD157	
0020	22		PA		3-4	23-15-12	D10859A	H02		D41619J		4		YC051-YD157	
0021	22		PA		3-4	23-15-12	D10859A	E02		D41619J		7		YC051-YD157	
0022	24		GK		2-4	23-15-12	D10857B	E06		D10859A	C01			YC051-YC062	
0023	24		GK		2-4	23-15-12	D10857B	F06		D10859A	D01			YC051-YC062	
0024	24		GK		2-4	23-15-12	D10857B	G04		D10859A	A01			YC051-YC062	
0025	24		GK		2-4	23-15-12	D10857B	H04		D10859A	B01			YC051-YC062	
0026	22		PA		2-7	23-15-15	D10857B	B14		D06105J		1		YC051-YD157	
0027	22		PA		1-8	23-15-15	D10857B	C14		GD06102	DC..	1		YC051-YD157	
0028	22		PA		2-7	23-15-15	D10857B	A08		D06105J		4		YC051-YD157	
0029	24		PK		2-7	23-15-15	D10857B	C11		D06105J		17		YC051-YD157	
002CO				CB	0-0	23-15-12	D10857C	= C12		D10871	= C1			YC051-YD157	
002CX			OF	CB	1-4	23-15-12	D10857C	12	DN	D10871	= A1			YC051-YD157	
0030	24		PK		2-7	23-15-15	D10857B	E08		D06105J		18		YC051-YD157	
0031	24		PK		2-7	23-15-15	D10857B	D11		D06105J		19		YC051-YD157	

WIRE LIST

D280A108

91-21-11

Section W0610

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0613	286A0613				E6-1 ELECTRONIC SHELF (SATCOM) (continued)											
0032	24		PK		2-7	23-15-15		D10857B	G08			D06105J	20			YC051-YD157
0033	20		PA		2-4	23-15-11		D41601J	1			TB6101Z	A021	1A		YC051-YD157
003CO				CC	0-0	23-15-13		D10857C	= C13			D41621J	= C1			YC051-YD157
003CX			OF	CC	1-10	23-15-13		D10857C	13	DN		D41621J	= A1			YC051-YD157
0057	24		PK		0-7	23-15-12		D10859A	B05			D10859A	D05			YC058-YD157
2001B	24		Y2	AA	2-7	34-21-13		D10857B	B06			D06105J	3			YC051-YD157
2001R	24		Y2	AA	0-0	34-21-13		D10857B	A06			D06105J	2			YC051-YD157
2001Z				AA	0-0	34-21-13		D10857B	DED			D06105J	S/R			YC051-YD157
2002B	22		X2	AB	2-10	23-27-15		D10857B	H01			D06103J	3			YC051-YD157
2002R	22		X2	AB	0-0	23-27-15		D10857B	G01			D06103J	2			YC051-YD157
2002Z				AB	0-0	23-27-15		D10857B	PERG	1A		D06103J	S/R			YC051-YD157
2003B	22		X2	AC	2-10	23-15-12		D10857B	K01			D06103J	5			YC051-YD157
2003R	22		X2	AC	0-0	23-15-12		D10857B	J01			D06103J	4			YC051-YD157
2003Z				AC	0-0	23-15-12		D10857B	PERG	1A		D06103J	S/R			YC051-YD157
2004B	24		N6	AD	2-10	23-15-12		D10857B	F02			D06103J	11			YC051-YC057
2004B	24		Y2	AD	2-10	23-15-12		TB6101Y	B029	1A		D06103J	11			YC058-YD157
2004R	24		N6	AD	0-0	23-15-12		D10857B	E02			D06103J	10			YC051-YC057
2004R	24		Y2	AD	0-0	23-15-12		TB6101Y	A029	1A		D06103J	10			YC058-YD157
2004Z				AD	0-0	23-15-12		D10857B	DED			D06103J	20			YC051-YC057
2004Z				AD	0-0	23-15-12		TB6101Y	A031	1A		D06103J	20			YC058-YD157
2005B	24		N6	AE	2-10	23-15-12		D10857B	B02			D06103J	13			YC051-YC057
2005B	24		Y2	AE	2-10	23-15-12		TB6101Y	A033	1A		D06103J	13			YC058-YD157
2005R	24		N6	AE	0-0	23-15-12		D10857B	A02			D06103J	12			YC051-YC057
2005R	24		Y2	AE	0-0	23-15-12		TB6101Y	B033	1A		D06103J	12			YC058-YD157
2005Z				AE	0-0	23-15-12		D10857B	DED			D06103J	21			YC051-YC057
2005Z				AE	0-0	23-15-12		TB6101Y	A035	1A		D06103J	21			YC058-YD157
2006B	24		N6	AF	3-3	23-15-12		D10859B	B06			D41619J	12			YC051-YC062
2006B	24		Y2	AF	3-3	23-15-12		D10859B	A06			D41619J	12			YC063-YD157
2006R	24		N6	AF	0-0	23-15-12		D10859B	B05			D41619J	11			YC051-YC062
2006R	24		Y2	AF	0-0	23-15-12		D10859B	A05			D41619J	11			YC063-YD157
2006Z				AF	0-0	23-15-12		D10859B	B07			D41619J	S/R			YC051-YC062
2006Z				AF	0-0	23-15-12		D10859B	A07			D41619J	S/R			YC063-YD157
2007B	24		GL	AG	3-3	23-15-12		D10859B	K07			D41619J	6			YC051-YC062
2007B	22		PB	AG	3-3	23-15-12		D10859B	K07			D41619J	6			YC063-YD157
2007R	24		GL	AG	0-0	23-15-12		D10859B	K06			D41619J	5			YC051-YC062
2007R	22		PB	AG	0-0	23-15-12		D10859B	K06			D41619J	5			YC063-YD157
2008B	24		N6	AH	3-3	23-15-12		D10859B	A06			D41619J	9			YC051-YC062
2008B	24		Y2	AH	3-3	23-15-12		D10859B	B06			D41619J	9			YC063-YD157
2008R	24		N6	AH	0-0	23-15-12		D10859B	A05			D41619J	8			YC051-YC062

WIRE LIST

D280A108

91-21-11

Section W0610

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0613	286A0613			E6-1 ELECTRONIC SHELF (SATCOM) (continued)											
2008R	24	Y2	AH		0-0	23-15-12	D10859B	B05			D41619J	8			YC063-YD157
2008Z			AH		0-0	23-15-12	D10859B	A07			D41619J	S/R			YC051-YC062
2008Z			AH		0-0	23-15-12	D10859B	B07			D41619J	S/R			YC063-YD157
2009B	24	Y2	AI		2-10	23-15-13	D10857B	D02			D06103J	15			YC051-YD157
2009R	24	Y2	AI		0-0	23-15-13	D10857B	C02			D06103J	14			YC051-YD157
2009Z			AI		0-0	23-15-13	D10857B	DED			D06103J	16			YC051-YD157
2010B	24	Y2	AJ		2-10	23-15-13	D10857B	H02			D06103J	18			YC051-YD157
2010R	24	Y2	AJ		0-0	23-15-13	D10857B	G02			D06103J	17			YC051-YD157
2010Z			AJ		0-0	23-15-13	D10857B	DED			D06103J	19			YC051-YD157
2011B	22	X2	AK		2-7	23-15-15	D10857B	D07			D06105J	6			YC051-YD157
2011R	22	X2	AK		0-0	23-15-15	D10857B	C07			D06105J	5			YC051-YD157
2011Z			AK		0-0	23-15-15	D10857B	DED			D06105J	S/R			YC051-YD157
2012B	22	X2	AL		2-7	34-61-18	D10857B	B07			D06105J	8			YC051-YC058
2012B	22	X2	AL		2-7	31-32-15	D10857B	B07			D06105J	8			YC059-YD157
2012R	22	X2	AL		0-0	34-61-18	D10857B	A07			D06105J	7			YC051-YC058
2012R	22	X2	AL		0-0	31-32-15	D10857B	A07			D06105J	7			YC059-YD157
2012Z			AL		0-0	34-61-18	D10857B	DED			D06105J	S/R			YC051-YC058
2012Z			AL		0-0	31-32-15	D10857B	DED			D06105J	S/R			YC059-YD157
2013B	24	Y2	AM		2-7	34-61-23	D10857B	D03			D06105J	10			YC051-YD157
2013R	24	Y2	AM		0-0	34-61-23	D10857B	C03			D06105J	9			YC051-YD157
2013Z			AM		0-0	34-61-23	D10857B	DED			D06105J	S/R			YC051-YD157
2014B	24	Y2	AN		2-7	23-15-15	D10857B	K03			D06105J	12			YC051-YD157
2014R	24	Y2	AN		0-0	23-15-15	D10857B	J03			D06105J	11			YC051-YD157
2014Z			AN		0-0	23-15-15	D10857B	PERG 1A			D06105J	S/R			YC051-YD157
2015B	24	Y2	AO		2-7	34-61-23	D10857B	F03			D06105J	14			YC051-YD157
2015R	24	Y2	AO		0-0	34-61-23	D10857B	E03			D06105J	13			YC051-YD157
2015Z			AO		0-0	34-61-23	D10857B	DED			D06105J	S/R			YC051-YD157
2016B	24	Y2	AP		2-7	SPARE	D10857B	CAP	Y		D06105J	16			YC051-YD157
2016R	24	Y2	AP		0-0	SPARE	D10857B	CAP	Y		D06105J	15			YC051-YD157
2016Z			AP		0-0	SPARE	D10857B	DED			D06105J	S/R			YC051-YD157
2031B	24	Y2	BF		2-0	23-15-12	TB6101Y	B029	1A		D10857B	F02			YC058-YD157
2031R	24	Y2	BF		0-0	23-15-12	TB6101Y	A029	1A		D10857B	E02			YC058-YD157
2031Z			BF		0-0	23-15-12	TB6101Y	A031	1A		D10857B	DED			YC058-YD157
2032B	24	Y2	BG		2-0	23-15-12	TB6101Y	A033	1A		D10857B	B02			YC058-YD157
2032R	24	Y2	BG		0-0	23-15-12	TB6101Y	B033	1A		D10857B	A02			YC058-YD157
2032Z			BG		0-0	23-15-12	TB6101Y	A035	1A		D10857B	DED			YC058-YD157
2037B	24	Y2	BJ		2-4	23-15-12	D10857B	H04			D10859A	B01			YC063-YD157
2037R	24	Y2	BJ		0-0	23-15-12	D10857B	G04			D10859A	A01			YC063-YD157
2037Z			BJ		0-0	23-15-12	D10857B	PERG 1A			D10859A	DED			YC063-YD157

WIRE LIST

D280A108

91-21-11

Section W0610

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0613 286A0613 E6-1 ELECTRONIC SHELF (SATCOM) (continued)															
2038B	24		Y2	BK	2-4	23-15-12	D10857B	F06			D10859A	D01			YC063-YD157
2038R	24		Y2	BK	0-0	23-15-12	D10857B	E06			D10859A	C01			YC063-YD157
2038Z				BK	0-0	23-15-12	D10857B	PERG	1A		D10859A	DED			YC063-YD157
W0619 286A0619 E6-1 ELECTRONIC SHELF; CODING															
0001	24		PK		2-7	23-15-15	D10857B	C13			D03963	1			YC051-YD157
0002	24		PK		2-7	23-15-15	D10857B	D13			D03963	2			YC051-YD157
0003	24		PK		2-7	23-15-15	D10857B	E13			D03963	3			YC051-YC052, YD154-YD157
0003	24		PK		2-7	23-15-15	D10857B	E13			D03963	3	VP		YC053-YD153
0004	24		PK		2-7	23-15-15	D10857B	F13			D03963	4			YC051-YC052, YD154-YD157
0004	24		PK		2-7	23-15-15	D10857B	F13			D03963	4	VP		YC053-YD153
0005	24		PK		2-7	23-15-15	D10857B	G13			D03963	5			YC051-YC052, YD154-YD157
0005	24		PK		2-7	23-15-15	D10857B	G13			D03963	5	VP		YC053-YD153
0006	24		PK		2-7	23-15-15	D10857B	H13			D03963	6			YC051-YC052, YD154-YD157
0006	24		PK		2-7	23-15-15	D10857B	H13			D03963	6	VP		YC053-YD153
0007	24		PK		2-7	23-15-15	D10857B	J13			D03963	7			YC051-YD157
0008	24		PK		2-7	23-15-15	D10857B	K13			D03963	8			YC051-YD157
0009	24		PK		2-7	23-15-15	D10857B	D14			D03963	9			YC051-YD157
0010	24		PK		2-7	23-15-15	D10857B	E14			D03963	10			YC051-YC052, YD154-YD157
0010	24		PK		2-7	23-15-15	D10857B	E14			D03963	10	VP		YC053-YD153
0011	24		PK		2-7	23-15-15	D10857B	F14			D03963	11			YC051-YD157
0012	24		PK		2-7	23-15-15	D10857B	G14			D03963	12			YC051-YD157
0013	24		PK		2-7	23-15-15	D10857B	H14			D03963	13			YC051-YC052, YD154-YD157
0013	24		PK		2-7	23-15-15	D10857B	H14			D03963	13	VP		YC053-YD153
0014	24		PK		2-7	23-15-15	D10857B	J14			D03963	14			YC051-YD157
0015	24		PK		2-7	23-15-15	D10857B	K14			D03963	15			YC051-YD157
0016	24		PK		2-7	23-15-15	D10857B	A15			D03963	16			YC051-YD157
0017	24		PK		2-7	23-15-15	D10857B	B15			D03963	17			YC051-YD157
0018	24		PK		2-7	23-15-15	D10857B	C15			D03963	18			YC051-YC068, YD154-YD157
0018	24		PK		2-7	23-15-15	D10857B	C15			D03963	18	VP		YC070-YD153
0019	24		PK		2-7	23-15-15	D10857B	D15			D03963	19			YC051-YC052, YC070-YD157

WIRE LIST

D280A108

91-21-11

Section W0610

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0619	286A0619				E6-1 ELECTRONIC SHELF; CODING (continued)										
0019	24		PK		2-7	23-15-15	D10857B	D15			D03963	19	VP		YC053-YC068
0020	24		PK		2-7	23-15-15	D10857B	E15			D03963	20			YC051-YC052, YC064-YD157
0020	24		PK		2-7	23-15-15	D10857B	E15			D03963	20	VP		YC053-YC063
0021	24		PK		2-7	23-15-15	D10857B	F15			D03963	21			YC051-YC060, YC064-YD157
0021	24		PK		2-7	23-15-15	D10857B	F15			D03963	21	VP		YC061-YC063
0022	24		PK		2-7	23-15-15	D10857B	G15			D03963	22			YC051-YC056, YC061-YC064, YC070-YD151, YD154-YD157
0022	24		PK		2-7	23-15-15	D10857B	G15			D03963	22	VP		YC057-YC060, YC065-YC068, YD152-YD153
0023	24		PK		2-7	23-15-15	D10857B	H15			D03963	23			YC051-YC054, YC057-YC058, YC061-YC062, YC065, YD152-YD157
0023	24		PK		2-7	23-15-15	D10857B	H15			D03963	23	VP		YC055-YC056, YC059-YC060, YC063-YC064, YC067-YD151
0024	24		PK		2-7	23-15-15	D10857B	J15			D03963	24			YC051-YC053, YC055, YC057, YC059, YC061, YC063, YC065-YC067, YC070, YD152, YD154-YD157
0024	24		PK		2-7	23-15-15	D10857B	J15			D03963	24	VP		YC054, YC056, YC058, YC060, YC062, YC064, YC068, YD151, YD153
0025	24		PK		2-7	23-15-15	D10857B	K15			D03963	25			YC051-YD157
0030	24		PK		2-9	23-15-15	D10857A	A11			D03963	30			YC051-YC063
0031	24		PK		2-9	23-15-15	D10857A	C11			D03963	31			YC051-YD157
0032	24		PK		2-9	23-15-15	D10857A	H11			D03963	32			YC051-YD157
0033	24		PK		2-9	23-15-15	D10857A	G12			D03963	33			YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0610

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0619	286A0619			E6-1 ELECTRONIC SHELF; CODING (continued)											
0034	24		PK		2-9	23-15-15	D10857A		J12		D03963		34		YC051-YD157
0035	24		PK		2-9	23-15-15	D10857A		K12		D03963		35		YC051-YD157
0036	24		PK		2-9	23-15-15	D10857A		A13		D03963		36		YC051-YD157
0037	24		PK		2-9	23-15-15	D10857A		B13		D03963		37		YC051-YD157
0038	24		PK		2-9	23-15-15	D10857A		F13		D03963		38		YC051-YD157
0039	24		PK		2-9	23-15-15	D10857A		H13		D03963		39		YC051-YD157
0040	24		PK		2-9	23-15-15	D10857A		J11		D03963		40		YC051-YD157
0041	24		PK		2-9	23-15-15	D10857A		K11		D03963		41		YC051-YD157

WIRE LIST
D280A108

91-21-11
Section W0610
Page 6 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Fam	Diagram	From				To				Effectivity
	Wire No.	GA	CO TY				Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W0621	286A0621			E6-2 ELECTRONIC SHELF											
0002	20	PA			2-4	23-11-11	D00345C		2			D40111J	6		YL951-YR328
0003	20	PA			2-4	23-11-11	D40111J		7			D00345C	3		YL951-YR328
0005	22	PA			2-6	23-11-11	D40113J		B04			D00345B	F05		YL951-YR328
0006	22	PA			2-6	23-11-11	D40113J		A05			D00345B	E05		YL951-YR328
0007	20	PA			2-4	23-11-11	D40111J		8			D00345C	7		YL951-YR328
0008	20	PA			1-4	23-11-11	D00345C		8			GD06201	AC..	1	YL951-YR328
0009	20	PA			2-5	23-11-11	D00345C		9			D40121J	F		YL951-YR328
0010	20	PA			1-4	23-11-11	D00345C		10			GD06201	ST..	1	YL951-YR328
0011	20	PA			2-5	23-11-11	D00345C		1			D40121J	G		YL951-YR328
0013	22	PA			1-10	23-11-11	D00345B		C01			TB0621Y	A001	1A	YL951-YR328
0014	22	PA			2-4	23-11-11	D40121J		A02			TB0621Y	A001	1A	YL951-YR328
0015	22	PA			2-7	23-11-11	D00345B		H05			D40121J	B03		YL951-YR328
0016	22	PA			2-7	23-11-11	D00345B		C05			D40121J	B01		YL951-YR328
0017	22	PA			2-7	23-11-11	D00345B		B05			D40121J	A01		YL951-YR328
0019	22	PA			2-1	23-11-11	D40117J		A10			TB0621Y	A001	1A	YL951-YR328
001CO				MA	0-0	23-11-11	D00345B		= C71			D40123J	= C1		YL951-YR328
001CX		0G		MA	1-11	23-11-11	D00345B		71			D40123J	= A1		YL951-YR328
0021	22	PA			2-7	23-11-11	D00345B		F04			D40121J	A04		YL951-YR328
0022	22	PA			2-7	23-11-11	D00345B		E04			D40121J	B04		YL951-YR328
0023	24	PK			0-7	23-11-11	D00345B		J04			D00345B	K04		YL951-YR328
002CO				MB	0-0	23-11-21	D00623B		= C71			D40127J	= C1		YL951-YR328
002CX		0G		MB	2-7	23-11-21	D00623B		71			D40127J	= A1		YL951-YR328
0069	22	PA			1-5	23-11-11	D00345B		D05			GD06201	DC..	1	YL951-YR328
0085	24	PK			2-4	31-31-17	D00345B		E02			D40117J	B07		YL951-YR328
0086	24	G6			3-0	31-31-17	D40119J		B04			D00623B	E02		YL951-YR328
0129	22	PA			1-5	23-11-11	D00345B		K02			GD06201	DC..	1	YL951-YR328
0130	22	PA			1-5	23-11-11	D00345B		J05			GD06201	DC..	1	YL951-YR328
0138	24	B6			2-6	23-12-41	D40113J		B05			D00345B	J03		YL951-YR328
0146	20	G5			2-11	23-11-21	D40621J		1			D00623C	7		YL951-YR328
0147	20	G5			2-11	23-11-21	D40621J		2			D00623C	3		YL951-YR328
0148	20	G5			2-11	23-11-21	D40621J		3			D00623C	2		YL951-YR328
0149	20	G5			1-4	23-11-21	D00623C		8			GD06202	AC..	1	YL951-YR328
0150	20	G5			1-4	23-11-21	D00623C		10			GD06202	ST..	1	YL951-YR328
0161	24	G6			0-7	23-11-21	D00623B		H04			D00623B	K04		YL951-YR328
0162	22	G5			1-5	23-11-21	D00623B		J05			GD06202	DC..	1	YL951-YR328
0163	22	G5			1-5	23-11-21	D00623B		K02			GD06202	DC..	1	YL951-YR328
0164	22	G5			1-5	23-11-21	D00623B		D05			GD06202	DC..	1	YL951-YR328
0168	20	G5			3-0	23-11-21	D00623C		9			D40125J	F		YL951-YR328
0169	20	G5			3-0	23-11-21	D00623C		1			D40125J	G		YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0620

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0621	286A0621				E6-2 ELECTRONIC SHELF (continued)											
0170	22		G5		3-2	23-11-21		D00623B	H05			D40125J	B03			YL951-YR328
0171	22		G5		3-2	23-11-21		D00623B	C05			D40125J	B01			YL951-YR328
0172	22		G5		3-2	23-11-21		D00623B	B05			D40125J	A01			YL951-YR328
0173	22		G5		2-3	23-11-21		D40125J	A02			TB0621Y	B001	1A		YL951-YR328
0174	22		PA		2-2	23-11-21		D40119J	B02			TB0621Y	B001	1A		YL951-YR328
0175	22		PA		1-11	23-11-21		D00623B	C01			TB0621Y	B001	1A		YL951-YR328
0176	22		G5		3-0	23-11-21		D40115J	B02			D00623B	F05			YL951-YR328
0177	22		G5		3-0	23-11-21		D40115J	A03			D00623B	E05			YL951-YR328
0178	24		G6		3-0	23-12-41		D00623B	J03			D40115J	B03			YL951-YR328
0182	22		G5		3-2	23-11-21		D00623B	E04			D40125J	B05			YL951-YR328
0183	22		G5		3-2	23-11-21		D00623B	F04			D40125J	B04			YL951-YR328
2020B	24		M5	EU	2-4	23-22-11		D00345B	D03			D40117J	B03			YL951-YR328
2020R	24		M5	EU	0-0	23-22-11		D00345B	C03			D40117J	A03			YL951-YR328
2020ZI				EU	0-0	23-22-11		D00345B	DED			D40117J	A04			YL951-YR328
2020ZO				EU	0-0	23-22-11		GB00621	ST..	1A		D40117J	PERG	1F		YL951-YR328
2021B	24		M5	EV	3-0	23-22-11		D40119J	B05			D00623B	D03			YL951-YR328
2021R	24		M5	EV	0-0	23-22-11		D40119J	A05			D00623B	C03			YL951-YR328
2021ZI				EV	0-0	23-22-11		D40119J	A06			D00623B	DED			YL951-YR328
2021ZO				EV	0-0	23-22-11		D40119J	PERG	1F		D00623B	PERG	1A		YL951-YR328
2501B	24		M5	AA	2-4	23-11-11		D00345B	E01			D40117J	B01			YL951-YR328
2501R	24		M5	AA	0-0	23-11-11		D00345B	D01			D40117J	A01			YL951-YR328
2501ZI				AA	0-0	23-11-11		D00345B	DED			D40117J	A02			YL951-YR328
2501ZO				AA	0-0	23-11-11		GB00621	ST..	1A		D40117J	PERG	1F		YL951-YR328
2502B	24		M5	AB	2-4	23-11-11		D00345B	B01			D40117J	B06			YL951-YR328
2502R	24		M5	AB	0-0	23-11-11		D00345B	A01			D40117J	A06			YL951-YR328
2502ZI				AB	0-0	23-11-11		D00345B	DED			D40117J	A07			YL951-YR328
2502ZO				AB	0-0	23-11-11		GB00621	ST..	1A		D40117J	PERG	1F		YL951-YR328
2506B	24		Y2	AF	2-6	23-11-11		D00345B	D04			D40113J	B03			YL951-YR328
2506R	24		Y2	AF	0-0	23-11-11		D00345B	C04			D40113J	A03			YL951-YR328
2506Z				AF	0-0	23-11-11		GB00621	ST..	1A		D40113J	PERG	1F		YL951-YR328
2508B	24		Y2	AH	1-10	23-12-41		D00345B	F03			TB0621Y	B003	1A		YL951-YR328
2508R	24		Y2	AH	0-0	23-12-41		D00345B	E03			TB0621Y	A003	1A		YL951-YR328
2508Z				AH	0-0	23-12-41		GB00621	ST..	1A		GB00621	ST..	1A		YL951-YR328
2509B	24		Y2	AI	1-11	23-12-41		D00345B	H03			TB0621Y	B005	1A		YL951-YR328
2509R	24		Y2	AI	0-0	23-12-41		D00345B	G03			TB0621Y	A005	1A		YL951-YR328
2509Z				AI	0-0	23-12-41		GB00621	ST..	1A		GB00621	ST..	1A		YL951-YR328
2510B	24		Y2	AJ	2-3	23-12-41		D40113J	B02			TB0621Y	B005	1A		YL951-YR328
2510R	24		Y2	AJ	0-0	23-12-41		D40113J	A02			TB0621Y	A005	1A		YL951-YR328
2510Z				AJ	0-0	23-12-41		D40113J	PERG	1F		GB00621	ST..	1A		YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0620

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice Effectivity

W0621	286A0621	E6-2 ELECTRONIC SHELF (continued)												
2511B	24	Y2	AK	2-3	23-12-41	D40113J	B01				TB0621Y	B003	1A	YL951-YR328
2511R	24	Y2	AK	0-0	23-12-41	D40113J	A01				TB0621Y	A003	1A	YL951-YR328
2511Z			AK	0-0	23-12-41	D40113J	PERG	1F			GB00621	ST..	1A	YL951-YR328
2516B	24	M5	AR	3-0	23-11-21	D00623B	E01				D40119J	B03		YL951-YR328
2516R	24	M5	AR	0-0	23-11-21	D00623B	D01				D40119J	A03		YL951-YR328
2516ZI			AR	0-0	23-11-21	D00623B	DED				D40119J	A04		YL951-YR328
2516ZO			AR	0-0	23-11-21	D00623B	PERG	1A			D40119J	PERG	1F	YL951-YR328
2517B	24	M5	AS	3-0	23-11-21	D00623B	B01				D40119J	B01		YL951-YR328
2517R	24	M5	AS	0-0	23-11-21	D00623B	A01				D40119J	A01		YL951-YR328
2517ZI			AS	0-0	23-11-21	D00623B	DED				D40119J	A02		YL951-YR328
2517ZO			AS	0-0	23-11-21	D00623B	PERG	1A			D40119J	PERG	1F	YL951-YR328
2519B	24	Y2	AU	1-11	23-12-41	D00623B	H03				TB0621Y	B003	1A	YL951-YR328
2519R	24	Y2	AU	0-0	23-12-41	D00623B	G03				TB0621Y	A003	1A	YL951-YR328
2519Z			AU	0-0	23-12-41	D00623B	PERG	1A			GB00621	ST..	1A	YL951-YR328
2529B	24	Y2	BD	1-11	23-12-41	D00623B	F03				TB0621Y	B005	1A	YL951-YR328
2529R	24	Y2	BD	0-0	23-12-41	D00623B	E03				TB0621Y	A005	1A	YL951-YR328
2529Z			BD	0-0	23-12-41	D00623B	PERG	1A			GB00621	ST..	1A	YL951-YR328
2530B	24	Y2	BE	3-0	23-11-21	D40115J	B01				D00623B	D04		YL951-YR328
2530R	24	Y2	BE	0-0	23-11-21	D40115J	A01				D00623B	C04		YL951-YR328
2530Z			BE	0-0	23-11-21	D40115J	PERG	1F			D00623B	PERG	1A	YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W0620

Page 3 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W0737	286A0737			E5-2 TO P59 FMC DIP SWITCH												
0001	22	PA		1-7	34-61-19	D45221J	A01				M01990	1	1A		ALL	
0002	22	PA		1-7	34-61-19	D45221J	A02				M01990	2	1A		ALL	
0003	22	PA		1-7	34-61-19	D45221J	A03				M01990	3	1A		ALL	
0004	22	PA		1-7	34-61-19	D45221J	A04				M01990	4	1A		ALL	
0005	22	PA		1-7	34-61-19	D45221J	A05				M01990	5	1A		ALL	
0006	22	PA		1-7	34-61-19	D45221J	A06				M01990	6	1A		ALL	
0007	22	PA		1-7	34-61-19	D45221J	A07				M01990	7	1A		ALL	
0008	22	PA		1-7	34-61-19	D45221J	A08				M01990	8	1A		ALL	
0009	22	PA		1-8	34-61-19	D45221J	A09				M01990	9	1A		ALL	
0010	22	PA		1-8	34-61-19	D45221J	A10				M01990	10	1A		ALL	
0011	22	PA		1-8	34-61-19	D45221J	A11				M01990	11	1A		ALL	
0012	22	PA		1-8	34-61-19	D45221J	A12				M01990	12	1A		ALL	
0013	22	PA		1-7	34-61-19	D45221J	A13				M01991	1	1A		YC051-YD158	
0013	22	PA		1-9	34-61-19	D45221J	A13				M01991	1	1A		YD160-YR328	
0015	22	PA		1-7	34-61-19	D45221J	A15				M01991	3	1A		YC051-YD158	
0015	22	PA		1-9	34-61-19	D45221J	A15				M01991	3	1A		YD160-YR328	
0016	22	PA		1-7	34-61-19	D45221J	A16				M01991	4	1A		YC051-YD158	
0016	22	PA		1-9	34-61-19	D45221J	A16				M01991	4	1A		YD160-YR328	
0017	22	PA		1-7	34-61-19	D45221J	A17				M01991	5	1A		YC051-YD158	
0017	22	PA		1-9	34-61-19	D45221J	A17				M01991	5	1A		YD160-YR328	
0018	22	PA		1-7	34-61-19	D45221J	A18				M01991	6	1A		YC051-YD158	
0018	22	PA		1-9	34-61-19	D45221J	A18				M01991	6	1A		YD160-YR328	
0019	22	PA		1-7	34-61-19	D45221J	A19				M01991	7	1A		YC051-YD158	
0019	22	PA		1-9	34-61-19	D45221J	A19				M01991	7	1A		YD160-YR328	
0020	22	PA		1-7	34-61-19	D45221J	A20				M01991	8	1A		YC051-YD158	
0020	22	PA		1-9	34-61-19	D45221J	A20				M01991	8	1A		YD160-YR328	
0021	22	PA		1-8	34-61-19	D45221J	B01				M01991	9	1A		ALL	
0022	22	PA		1-8	34-61-19	D45221J	B02				M01991	10	1A		ALL	
0023	22	PA		1-8	34-61-19	D45221J	B03				M01991	11	1A		ALL	
0024	22	PA		1-8	34-61-19	D45221J	B04				M01991	12	1A		ALL	
0026	22	PA		1-10	34-61-12	D45221J	B06				TB0591X	A001	1A		ALL	
0027	22	PA		1-10	34-61-12	D45221J	B07				TB0591X	A001	1A		ALL	
0028	22	PA		1-10	34-61-12	D45221J	B08				TB0591X	A003	1A		ALL	
0029	22	PA		1-10	34-61-12	D45221J	B09				TB0591X	A003	1A		ALL	
0030	22	PA		1-10	34-61-12	D45221J	B10				TB0591X	B001	1A		ALL	
0031	22	PA		1-10	34-61-12	D45221J	B11				TB0591X	B001	1A		ALL	
0032	22	PA		1-10	34-61-12	D45221J	B12				TB0591X	B003	1A		ALL	
0033	22	PA		1-10	34-61-12	D45221J	B13				TB0591X	B003	1A		ALL	
0034	22	PA		1-7	34-61-19	D45221J	B14				M01990	13	1A		YC053-YD158	

WIRE LIST

D280A108

91-21-11

Section W0730

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0737		286A0737			E5-2 TO P59 FMC DIP SWITCH (continued)											
0034		22		PA		1-8	34-61-19	D45221J	B14			M01990	13	1A		YD160-YR328
0035		22		PA		1-7	34-61-19	D45221J	B15			M01990	14	1A		YC053-YD158
0035		22		PA		1-8	34-61-19	D45221J	B15			M01990	14	1A		YD160-YR328
0036		22		PA		1-3	34-61-19	M01990	25	1A		GD01047	DC..	E		ALL
0037		22		PA		1-3	34-61-19	M01991	25	1A		GD01047	DC..	E		YC051-YD158
0037		22		PA		1-6	34-61-19	M01991	25	1A		GD01047	DC..	E		YD160-YR328
0038		22		PA		1-8	34-61-19	D45221J	B16			M01990	15	1A		YD160-YR328
0039		22		PA		1-8	34-61-19	D45221J	B17			M01990	16	1A		YD160-YR328

WIRE LIST

D280A108

91-21-11

Section W0730

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0767	286A0767			D43267J TO FLIGHT RECORDER M96											
0001	22	PA		1-6	31-31-11	D43267J		12			D00183A	21			ALL
0002	22	PA		1-6	31-31-11	D43267J		13			D00183A	22			ALL
0003	20	PA		1-6	31-31-11	D43267J		11			D00183A	17			ALL
0004	20	PA		1-6	31-31-11	D43267J		10			D00183A	6			ALL
0005	20	PA		1-6	31-31-11	D43267J		9			D00183A	2			ALL
0007	22	PA		1-6	31-31-11	D43267J		7			D00183A	1			ALL
0008	22	PA		1-6	31-31-11	D43267J		8			D00183A	23			ALL
2001B	22	X2	AA	1-6	31-31-11	D43267J		2			D00183A	10			ALL
2001R	22	X2	AA	0-0	31-31-11	D43267J		1			D00183A	9			ALL
2001Z			AA	0-0	31-31-11	D43267J		3			D00183A	DED			ALL
2002B	22	X2	AB	1-6	31-31-11	D43267J		5			D00183A	8			ALL
2002R	22	X2	AB	0-0	31-31-11	D43267J		4			D00183A	7			ALL
2002Z			AB	0-0	31-31-11	D43267J		6			D00183A	DED			ALL

WIRE LIST
D280A108

91-21-11
Section W0760
Page 1 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0811		286A0811				E8-1 ELECTRONIC SHELF									
0001		20		CQ	2-10	23-11-11	D40811J		6		TB0812Y	A039	1A		YC051-YC052
0001		20		CQ	2-7	23-11-11	D40811J		6		TB0812Y	A039	1A		YC053-YD157
0001		22		PA	4-1	44-21-22	D12391B		J08		D45905J		19		YN501-YR328
0002		20		CQ	1-11	23-11-11	D00345C		2		TB0812Y	A039	1A		YC051-YC052
0002		20		CQ	2-5	23-11-11	D00345C		2		TB0812Y	A039	1A		YC053-YD157
0002		20		PA	3-0	23-11-11	D00345C		2		D40811J		6		YD158-YD170
0003		20		CQ	2-7	23-11-11	D40811J		7		D00345C		3		YC051-YC052
0003		20		CQ	3-0	23-11-11	D40811J		7		D00345C		3		YC053-YD157
0003		20		PA	3-0	23-11-11	D40811J		7		D00345C		3		YD158-YD170
0004		20		CQ	1-8	23-11-11	D08511J		A01		TB0812Y	A039	1A		YC051-YC052
0004		20		CQ	3-6	23-11-11	D08511J		A01		TB0812Y	A039	1A		YC053-YD157
0005		22		PA	2-4	23-11-11	D08511J		A05		D00345B		E05		YC051-YC052
0005		22		PA	2-8	23-11-11	D08511J		A05		D00345B		E05		YC053-YD157
0005		22		PA	2-9	23-11-11	D40075J		B04		D00345B		F05		YD158-YD170
0006		22		PA	2-4	23-11-11	D08511J		B05		D00345B		F05		YC051-YC052
0006		22		PA	2-8	23-11-11	D08511J		B05		D00345B		F05		YC053-YD157
0006		22		PA	2-9	23-11-11	D40075J		A05		D00345B		E05		YD158-YD170
0007		20		CQ	2-7	23-11-11	D40811J		8		D00345C		7		YC051-YC052
0007		20		CQ	3-0	23-11-11	D40811J		8		D00345C		7		YC053-YD157
0007		20		PA	3-0	23-11-11	D40811J		8		D00345C		7		YD158-YD170
0008		20		PA	1-4	23-11-11	D00345C		8		GD08105	AC..	1A		YC051-YC052
0008		20		PA	2-5	23-11-11	D00345C		8		GD08103	AC..	1A		YC053-YD170
0009		20		PA	2-2	23-11-11	D00345C		9		D08509J		F		YC051-YC052
0009		20		PA	2-7	23-11-11	D00345C		9		D08509J		F		YC053-YD157
0009		20		PA	2-8	23-11-11	D00345C		9		D08509J		F		YD158-YD170
0010		20		G5	1-4	23-11-11	D00345C		10		GD08105	DC..	1A		YC051-YC052
0010		20		G5	2-5	23-11-11	D00345C		10		GD08103	DC..	1A		YC053-YD157
0010		20		PA	2-5	23-11-11	D00345C		10		GD08103	ST..	1A		YD158-YD170
0011		20		PA	2-2	23-11-11	D00345C		1		D08509J		G		YC051-YC052
0011		20		PA	2-7	23-11-11	D00345C		1		D08509J		G		YC053-YD157
0011		20		PA	2-8	23-11-11	D00345C		1		D08509J		G		YD158-YD170
0012		22		PA	2-4	23-11-11	D08511J		B01		D00345B		D05		YC051-YC052
0012		22		PA	2-8	23-11-11	D08511J		B01		D00345B		D05		YC053-YD157
0013		22		PA	2-0	23-11-11	D00345B		C01		TB0812Y	B039	1A		YC051-YC052
0013		22		PA	2-7	23-11-11	D00345B		C01		TB0812Y	B039	1A		YC053-YD157
0013		22		PA	2-10	23-11-11	D00345B		C01		TB0812Y	A017	1A		YD158-YD170
0014		22		PA	1-8	23-11-11	D08509J		A02		TB0812Y	B039	1A		YC051-YC052
0014		22		PA	3-6	23-11-11	D08509J		A02		TB0812Y	B039	1A		YC053-YD157
0014		22		PA	3-9	23-11-11	D08509J		A02		TB0812Y	A017	1A		YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0810

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0811	286A0811				E8-1 ELECTRONIC SHELF (continued)											
0015	22		PA		2-4	23-11-11		D00345B		H05		D08509J		B03		YC051-YC052
0015	22		PA		2-8	23-11-11		D00345B		H05		D08509J		B03		YC053-YD157
0015	22		PA		2-9	23-11-11		D00345B		H05		D08509J		B03		YD158-YD170
0016	22		PA		2-4	23-11-11		D00345B		C05		D08509J		B01		YC051-YC052
0016	22		PA		2-8	23-11-11		D00345B		C05		D08509J		B01		YC053-YD157
0016	22		PA		2-9	23-11-11		D00345B		C05		D08509J		B01		YD158-YD170
0017	22		PA		2-4	23-11-11		D00345B		B05		D08509J		A01		YC051-YC052
0017	22		PA		2-8	23-11-11		D00345B		B05		D08509J		A01		YC053-YD157
0017	22		PA		2-9	23-11-11		D00345B		B05		D08509J		A01		YD158-YD170
0018	22		PA		2-11	23-11-16		D40075J		A04		D00345A		J04		YD158-YD170
0019	24		PK		1-8	23-29-11		D08189J		A07		TB0812Y		B039	1A	YC051-YC052
0019	24		PK		3-6	23-29-11		D08189J		A07		TB0812Y		B039	1A	YC053-YD157
0019	22		PA		3-10	23-11-11		D08189J		A10		TB0812Y		A017	1A	YD158-YD170
001CO				MA	0-0	23-11-11		D00345B		= C71		D08517J		= C1		YC051-YD170
001CX			OG	MA	0-7	23-11-11		D00345B		71		D08517J		= A1		YC051-YC052
001CX			OG	MA	0-9	23-11-11		D00345B		71		D08517J		= A1		YC053-YD170
0020	22		PA		1-6	23-11-11		D00345B		J05		GD08105		DC..	1A	YC051-YC052
0020	22		PA		2-6	23-11-11		D00345B		J05		GD08103		DC..	1A	YC053-YD157
0020	22		PA		4-3	44-21-22		D12391A		H07		D45905J		6		YN501-YR328
0021	24		PK		2-4	23-11-11		D00345B		F04		D08509J		B04		YC051-YC052
0021	24		PK		2-8	23-11-11		D00345B		F04		D08509J		B04		YC053-YD157
0021	22		PA		2-9	23-11-11		D00345B		F04		D08509J		A04		YD158-YD170
0022	24		PK		2-4	23-11-11		D00345B		E04		D08509J		B05		YC051-YC052
0022	24		PK		2-8	23-11-11		D00345B		E04		D08509J		B05		YC053-YD157
0022	22		PA		2-9	23-11-11		D00345B		E04		D08509J		B04		YD158-YD170
0023	24		PK		0-7	23-11-11		D00345B		J04		D00345B		K04		YD158-YD170
0024	22		PA		3-1	44-21-22		D12391A		K12		D45912J		18		YN501-YR328
0025	22		PA		2-11	44-21-22		D12391B		K06		D45912J		15		YN501-YR328
0026	22		PA		2-11	44-21-22		D12391B		K07		D45912J		19		YN501-YR328
0027	22		PA		2-11	44-21-22		D12391B		F03		D45912J		20		YN501-YR328
002CO				MB	0-0	23-11-21		D00623B		= C71		D08823J		= C1		YD158-YD170
002CX			OG	MB	1-4	23-11-21		D00623B		71		D08823J		= A1		YD158-YD170
0036	20		PA		2-9	44-21-10		D12391C		1		D45912J		5		YN501-YR328
0037	20		PA		2-6	44-21-10		D12391C		4		GD08104		AC..	1A	YN501-YR328
0038	20		PA		1-10	44-21-10		D12391C		9		GD08105		ST..	1A	YN501-YR328
0042	22		PA		4-1	44-21-22		D12391B		G10		D45905J		20		YN501-YR328
0043	22		PA		4-1	44-21-22		D12391B		J06	VP	D45905J		21		YN501-YR328
0044	22		PA		4-1	44-21-22		D12391B		J07		D45905J		22		YN501-YR328
0045	22		PA		4-3	44-21-22		D12391A		H06		D45905J		2		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0810

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0811		286A0811			E8-1 ELECTRONIC SHELF (continued)											
0046		22		PA		3-1	44-21-22	D12391A		C03		D45912J		21		YN501-YR328
0047		22		PA		3-1	44-21-22	D12391A		K11		D45912J		16		YN501-YR328
0048		22		PA		2-11	44-21-22	D12391B		C01		D45912J		17		YN501-YR328
0069		22		PA		3-10	23-11-11	D00345B		D05		GD08105	DC..	1A		YD158-YD170
0071		22		PA		2-6	23-11-11	D00345B		K03		GD08103	DC..	1A		YC059-YD170
0072		22		PA		3-3	23-11-21	D00623B		K03		GD08105	DC..	1A		YD158-YD170
0085		24		PK		2-4	31-31-17	D00345B		E02		D08189J		B07		YC051-YC052
0085		24		PK		2-8	31-31-17	D00345B		E02		D08189J		B07		YC053-YD157
0085		24		G6		3-11	31-31-17	TB0812Y		A013	1A	D08189J		B07		YD158-YD170
0086		24		G6		3-3	31-31-17	TB0812Y		B013	1A	D08002J		B04		YD158-YD170
0109		20		PA		1-9	44-21-26	D45905J		23		D45920J		40		YN501-YR328
0110		22		PA		1-9	44-21-26	D45905J		24		D45920J		39		YN501-YR328
0111		22		PA		2-10	44-21-26	D45920J		53		GD08104	DC..	1A		YN501-YR328
0121		24		PK		2-5	23-11-16	D00623A		K07		TB0812Y	A013	1A		YD158-YD170
0122		24		PK		3-0	23-11-26	D00345A		K07		TB0812Y	B013	1A		YD158-YD170
0129		22		PA		3-10	23-11-11	D00345B		K02		GD08105	DC..	1A		YD158-YD170
0130		22		PA		3-10	23-11-11	D00345B		J05		GD08105	DC..	1A		YD158-YD170
0137		20		PA		4-1	23-11-16	D08189J		B10		TB0812Z	A001	1A		YD158-YD170
0138		24		PK		2-9	23-12-41	D40075J		B05		D00345B		J03		YD158-YD170
0139		22		PA		3-2	23-11-16	D00345B		G04		TB0812Z	A001	1A		YD158-YD170
0144		24		PK		2-4	23-11-26	TB0812Y		B013	1A	D00623B		E02		YD158-YD170
0145		24		PK		2-11	23-11-16	D00345B		E02		TB0812Y	A013	1A		YD158-YD170
0146		20		CQ		4-7	23-11-21	D48323J		1		D00623C		7		YD158-YD170
0147		20		CQ		4-7	23-11-21	D48323J		2		D00623C		3		YD158-YD170
0148		20		CQ		4-7	23-11-21	D48323J		3		D00623C		2		YD158-YD170
0149		20		G5		1-10	23-11-21	D00623C		8		GD08103	AC..	1A		YD158-YD170
0150		20		PA		1-10	23-11-21	D00623C		10		GD08103	ST..	1A		YD158-YD170
0160		22		PA		2-9	23-11-26	D00623A		J04		D40077J		A02		YD158-YD170
0161		24		PK		0-7	23-11-21	D00623B		H04		D00623B		K04		YD158-YD170
0162		22		PA		1-11	23-11-21	D00623B		J05		GD08103	DC..	1A		YD158-YD170
0163		22		PA		1-11	23-11-21	D00623B		K02		GD08103	DC..	1A		YD158-YD170
0164		22		PA		1-11	23-11-21	D00623B		D05		GD08103	DC..	1A		YD158-YD170
0166		22		PA		2-0	23-11-26	D00623A		G03		GD08103	DC..	1A		YD158-YD170
0167		22		PA		2-7	23-11-26	D00623B		G04		TB0812Z	A001	1A		YD158-YD170
0168		20		PA		2-7	23-11-21	D00623C		9		D08811J		F		YD158-YD170
0169		20		PA		2-7	23-11-21	D00623C		1		D08811J		G		YD158-YD170
0170		22		PA		2-8	23-11-21	D00623B		H05		D08811J		B03		YD158-YD170
0171		22		PA		2-8	23-11-21	D00623B		C05		D08811J		B01		YD158-YD170
0172		22		PA		2-8	23-11-21	D00623B		B05		D08811J		A01		YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0810

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0811	286A0811				E8-1 ELECTRONIC SHELF (continued)											
0173	22		PA		3-2	23-11-21		D08811J	A02			TB0812Y	A019	1A		YD158-YD170
0174	22		PA		3-2	23-11-21		D08002J	B02			TB0812Y	A019	1A		YD158-YD170
0175	22		PA		2-3	23-11-21		D00623B	C01			TB0812Y	A019	1A		YD158-YD170
0176	22		PA		2-8	23-11-21		D40077J	B02			D00623B	F05			YD158-YD170
0177	22		PA		2-8	23-11-21		D40077J	A03			D00623B	E05			YD158-YD170
0178	24		PK		2-8	23-12-41		D40077J	B03			D00623B	J03			YD158-YD170
0180	22		PA		2-7	23-11-16		D00345A	G03			GD08103	DC..	1A		YD158-YD170
0182	22		PA		2-8	23-11-21		D00623B	E04			D08811J	B05			YD158-YD170
0183	22		PA		2-8	23-11-21		D00623B	F04			D08811J	B04			YD158-YD170
0416	20		G5		3-0	23-34-01		TB0811Y	A001	1A		D48323J	11			YD158-YD170
2014B	24		Y2	AN	2-8	23-11-21		D00623B	D04			D40077J	B01			YD158-YD170
2014R	24		Y2	AN	0-0	23-11-21		D00623B	C04			D40077J	A01			YD158-YD170
2014Z				AN	0-0	23-11-21		D00623B	PERG	1A		D40077J	PERG	1F		YD158-YD170
2015B	24		Y2	AP	2-7	23-12-41		D00623B	F03			TB0812Y	B011	1A		YD158-YD170
2015R	24		Y2	AP	0-0	23-12-41		D00623B	E03			TB0812Y	A011	1A		YD158-YD170
2015Z				AP	0-0	23-12-41		D00623B	PERG	1A		GB00812	ST..	1A		YD158-YD170
2018B	24		M5	AT	2-8	23-11-21		D00623B	E01			D08002J	B03			YD158-YD170
2018R	24		M5	AT	0-0	23-11-21		D00623B	D01			D08002J	A03			YD158-YD170
2018ZI				AT	0-0	23-11-21		D00623B	DED			D08002J	A04			YD158-YD170
2018ZO				AT	0-0	23-11-21		D00623B	PERG	1A		D08002J	PERG	1F		YD158-YD170
2020B	24		M5	AV	2-4	23-22-11		D00345B	D03			D08189J	A03			YC051-YC052
2020B	24		M5	AV	2-8	23-22-11		D00345B	D03			D08189J	A03			YC053-YD157
2020B	24		M5	CS	2-9	23-22-11		D00345B	D03			D08189J	B03			YD158-YD170
2020R	24		M5	AV	0-0	23-22-11		D00345B	C03			D08189J	B03			YC051-YD157
2020R	24		M5	CS	0-0	23-22-11		D00345B	C03			D08189J	A03			YD158-YD170
2020ZI				AV	0-0	23-22-11		D00345B	DED			D08189J	A04			YC051-YD157
2020ZI				CS	0-0	23-22-11		D00345B	DED			D08189J	A04			YD158-YD170
2020ZO				AV	0-0	23-22-11		D00345B	PERG	1A		D08189J	PERG	1F		YC051-YD157
2020ZO				CS	0-0	23-22-11		D00345B	PERG	1A		D08189J	PERG	1F		YD158-YD170
2021B				CT	2-8	23-22-11		D00623B	D03			D08002J	B05			YD158-YD170
2021R	24		M5	CT	0-0	23-22-11		D00623B	C03			D08002J	A05			YD158-YD170
2021ZI				CT	0-0	23-22-11		D00623B	DED			D08002J	A06			YD158-YD170
2021ZO				CT	0-0	23-22-11		D00623B	PERG	1A		D08002J	PERG	1F		YD158-YD170
2022B	24		Y2	CB	3-0	34-61-14		D00345A	B07			D45023J	B01			YD158-YD170
2022R	24		Y2	CB	0-0	34-61-14		D00345A	A07			D45023J	A01			YD158-YD170
2022Z				CB	0-0	34-61-14		D00345A	PERG	1A		D45023J	PERG	1F		YD158-YD170
2023B	24		Y2	AX	2-10	34-61-14		D00623A	B07			D45025J	B01			YD158-YD170
2023R	24		Y2	AX	0-0	34-61-14		D00623A	A07			D45025J	A01			YD158-YD170
2023Z				AX	0-0	34-61-14		D00623A	PERG	1A		D45025J	PERG	1F		YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0810

Page 4

Nov 12/2012

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W0811	286A0811			E8-1 ELECTRONIC SHELF (continued)										
2024B	24	Y2	AY	3-0	34-61-15	D00345A	F07			D45023J	B02			YD158-YD170
2024R	24	Y2	AY	0-0	34-61-15	D00345A	E07			D45023J	A02			YD158-YD170
2024Z			AY	0-0	34-61-15	D00345A	PERG	1A		D45023J	PERG	1F		YD158-YD170
2025B	24	Y2	AZ	2-10	34-61-15	D00623A	F07			D45025J	B02			YD158-YD170
2025R	24	Y2	AZ	0-0	34-61-15	D00623A	E07			D45025J	A02			YD158-YD170
2025Z			AZ	0-0	34-61-15	D00623A	PERG	1A		D45025J	PERG	1F		YD158-YD170
2026B	24	Y2	BA	2-10	23-27-36	D00345A	B09			TB0812Y	B021	1A		YD158-YD170
2026R	24	Y2	BA	0-0	23-27-36	D00345A	A09			TB0812Y	A021	1A		YD158-YD170
2026Z			BA	0-0	23-27-36	D00345A	PERG	1A		GB00812	ST..	1A		YD158-YD170
2027B	24	Y2	BB	2-11	23-27-36	D00345A	D09			D40075J	B09			YD158-YD170
2027R	24	Y2	BB	0-0	23-27-36	D00345A	C09			D40075J	A09			YD158-YD170
2027Z			BB	0-0	23-27-36	D00345A	PERG	1A		D40075J	PERG	1F		YD158-YD170
2029B	24	Y2	BD	3-9	23-27-36	D40075J	B08			TB0812Y	B021	1A		YD158-YD170
2029R	24	Y2	BD	0-0	23-27-36	D40075J	A08			TB0812Y	A021	1A		YD158-YD170
2029Z			BD	0-0	23-27-36	D40075J	PERG	1F		GB00812	ST..	1A		YD158-YD170
2030B	24	Y2	BE	2-3	23-27-36	D00623A	B09			TB0812Y	B021	1A		YD158-YD170
2030R	24	Y2	BE	0-0	23-27-36	D00623A	A09			TB0812Y	A021	1A		YD158-YD170
2030Z			BE	0-0	23-27-36	D00623A	PERG	1A		GB00812	ST..	1A		YD158-YD170
2031B	24	Y2	BF	2-9	23-27-36	D00623A	D09			D40077J	B07			YD158-YD170
2031R	24	Y2	BF	0-0	23-27-36	D00623A	C09			D40077J	A07			YD158-YD170
2031Z			BF	0-0	23-27-36	D00623A	PERG	1A		D40077J	PERG	1F		YD158-YD170
2036B	24	Y2	BL	2-7	23-11-26	D00623A	C03			TB0812Y	B005	1A		YD158-YD170
2036R	24	Y2	BL	0-0	23-11-26	D00623A	B03			TB0812Y	A005	1A		YD158-YD170
2036Z			BL	0-0	23-11-26	D00623A	PERG	1A		GB00812	ST..	1A		YD158-YD170
2037B	24	Y2	BM	2-7	23-11-26	D00623A	D07			TB0812Y	B007	1A		YD158-YD170
2037R	24	Y2	BM	0-0	23-11-26	D00623A	C07			TB0812Y	A007	1A		YD158-YD170
2037Z			BM	0-0	23-11-26	D00623A	PERG	1A		GB00812	ST..	1A		YD158-YD170
2039B	24	Y2	BP	3-6	23-11-26	D40077J	B09			TB0812Y	B007	1A		YD158-YD170
2039R	24	Y2	BP	0-0	23-11-26	D40077J	A09			TB0812Y	A007	1A		YD158-YD170
2039Z			BP	0-0	23-11-26	D40077J	PERG	1F		GB00812	ST..	1A		YD158-YD170
2044B	24	Y2	AO	2-6	23-11-16	D00345A	H05			D00623A	K05			YD158-YD170
2044R	24	Y2	AO	0-0	23-11-16	D00345A	G05			D00623A	J05			YD158-YD170
2044Z			AO	0-0	23-11-16	D00345A	PERG	1A		D00623A	PERG	1A		YD158-YD170
2045B	24	Y2	AQ	2-6	23-11-26	D00623A	H05			D00345A	K05			YD158-YD170
2045R	24	Y2	AQ	0-0	23-11-26	D00623A	G05			D00345A	J05			YD158-YD170
2045Z			AQ	0-0	23-11-26	D00623A	PERG	1A		D00345A	PERG	1A		YD158-YD170
2501B	24	M5	AA	2-4	23-11-11	D00345B	E01			D08189J	A01			YC051-YC052
2501B	24	M5	AA	2-8	23-11-11	D00345B	E01			D08189J	A01			YC053-YD157
2501B	24	M5	AA	2-9	23-11-11	D00345B	E01			D08189J	B01			YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0810

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0811	286A0811			E8-1 ELECTRONIC SHELF (continued)											
2501R	24	M5	AA		0-0	23-11-11	D00345B	D01			D08189J	B01			YC051-YD157
2501R	24	M5	AA		0-0	23-11-11	D00345B	D01			D08189J	A01			YD158-YD170
2501ZI			AA		0-0	23-11-11	D00345B	DED			D08189J	A02			YC051-YD170
2501ZO			AA		0-0	23-11-11	GB08102	ST..	1A		D08189J	PERG	1F		YC051-YC052
2501ZO			AA		0-0	23-11-11	D00345B	PERG	1A		D08189J	PERG	1F		YC053-YD170
2502B		M5	AB		2-9	23-11-11	D00345B	B01			D08189J	B06			YD158-YD170
2502R	24	M5	AB		0-0	23-11-11	D00345B	A01			D08189J	A06			YD158-YD170
2502ZI			AB		0-0	23-11-11	D00345B	DED			D08189J	A07			YD158-YD170
2502ZO			AB		0-0	23-11-11	D00345B	PERG	1A		D08189J	PERG	1F		YD158-YD170
2503B	24	M5	AC		2-4	23-29-11	D08189J	A05			D00345B	B01			YC051-YC052
2503B	24	M5	AC		2-8	23-29-11	D08189J	A05			D00345B	B01			YC053-YD157
2503B	22	X2	AC		4-3	44-21-22	D12391A	F09			D45905J	17			YN501-YR328
2503R	24	M5	AC		0-0	23-29-11	D08189J	B05			D00345B	A01			YC051-YD157
2503R	22	X2	AC		0-0	44-21-22	D12391A	E09			D45905J	16			YN501-YR328
2503Z			AC		0-0	44-21-22	D12391A	PERB			D45905J	18			YN501-YR313
2503Z			AC		0-0	44-21-22	D12391A	PERB			D45905J	PERB			YR314-YR317
2503Z			AC		0-0	44-21-22	D12391A	PERB			D45905J			AE	YR318-YR328
2503ZI			AC		0-0	23-29-11	D08189J	A06			D00345B	DED			YC051-YD157
2503ZO			AC		0-0	23-29-11	D08189J	PERG	1F		D00345B	PERG	1A		YC051-YD157
2504B	24	Y2	AD		2-4	23-11-11	D08511J	B03			D00345B	H03			YC051-YC052
2504B	24	Y2	AD		2-8	23-11-11	D08511J	B03			D00345B	H03			YC053-YD157
2504B	22	X2	AD		4-3	44-21-22	D12391A	K03			D45905J	11			YN501-YR328
2504R	24	Y2	AD		0-0	23-11-11	D08511J	A03			D00345B	G03			YC051-YD157
2504R	22	X2	AD		0-0	44-21-22	D12391A	J03			D45905J	10			YN501-YR328
2504Z			AD		0-0	23-11-11	D08511J	PERG	1F		GB08102	ST..	1A		YC051-YC052
2504Z			AD		0-0	23-11-11	D08511J	PERG	1F		D00345B	PERG	1A		YC053-YD157
2504Z			AD		0-0	44-21-22	D12391A	PERB			D45905J	PERB			YN501-YR317
2504Z			AD		0-0	44-21-22	D12391A	PERB			D45905J			AE	YR318-YR328
2505B	22	X2	AE		4-3	44-21-22	D12391A	H05			D45905J	8			YN501-YR328
2505R	22	X2	AE		0-0	44-21-22	D12391A	H04			D45905J	7			YN501-YR328
2505Z			AE		0-0	44-21-22	D12391A	PERB			D45905J	PERB			YN501-YR317
2505Z			AE		0-0	44-21-22	D12391A	PERB			D45905J	DED			YR318-YR328
2506B	24	Y2	AF		2-9	23-11-11	D00345B	D04			D40075J	B03			YD158-YD170
2506R	24	Y2	AF		0-0	23-11-11	D00345B	C04			D40075J	A03			YD158-YD170
2506Z			AF		0-0	23-11-11	D00345B	PERG	1A		D40075J	PERG	1F		YD158-YD170
2507B	22	X2	AG		3-9	44-21-20	D12391A	H11			D45907J	16			YN501-YR328
2507R	22	X2	AG		0-0	44-21-20	D12391A	G11			D45907J	15			YN501-YR328
2507Z			AG		0-0	44-21-20	D12391A	PERB			D45907J	S/R			YN501-YR328
2508B	24	Y2	AH		3-2	23-12-41	D00345B	F03			TB0812Y	B009	1A		YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0810

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To			Effectivity				
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type		Splice	Equip	Term	Type
W0811	286A0811			E8-1 ELECTRONIC SHELF (continued)											
2508R	24	Y2	AH		0-0	23-12-41	D00345B	E03			TB0812Y	A009	1A		YD158-YD170
2508Z			AH		0-0	23-12-41	D00345B	PERG	1A		GB00812	ST..	1A		YD158-YD170
2509B	24	Y2	AI		3-2	23-12-41	D00345B	H03			TB0812Y	B011	1A		YD158-YD170
2509R	24	Y2	AI		0-0	23-12-41	D00345B	G03			TB0812Y	A011	1A		YD158-YD170
2509Z			AI		0-0	23-12-41	D00345B	PERG	1A		GB00812	ST..	1A		YD158-YD170
2510B	24	Y2	AJ		4-2	23-12-41	D40075J	B02			TB0812Y	B011	1A		YD158-YD170
2510R	24	Y2	AJ		0-0	23-12-41	D40075J	A02			TB0812Y	A011	1A		YD158-YD170
2510Z			AJ		0-0	23-12-41	D40075J	PERG	1F		GB00812	ST..	1A		YD158-YD170
2511B	24	Y2	AK		4-2	23-12-41	D40075J	B01			TB0812Y	B009	1A		YD158-YD170
2511B	22	X2	AK		3-9	44-21-20	D12391A	F10			D45907J	4			YN501-YR328
2511R	24	Y2	AK		0-0	23-12-41	D40075J	A01			TB0812Y	A009	1A		YD158-YD170
2511R	22	X2	AK		0-0	44-21-20	D12391A	E10			D45907J	3			YN501-YR328
2511Z			AK		0-0	23-12-41	D40075J	PERG	1F		GB00812	ST..	1A		YD158-YD170
2511Z			AK		0-0	44-21-20	D12391A	PERB			D45907J	S/R			YN501-YR328
2512B	22	X2	AL		4-3	44-21-22	D12391A	K06			D45905J	15			YN501-YR328
2512R	22	X2	AL		0-0	44-21-22	D12391A	J06			D45905J	14			YN501-YR328
2512Z			AL		0-0	44-21-22	D12391A	PERB			D45905J	PERB			YN501-YR317
2512Z			AL		0-0	44-21-22	D12391A	PERB			D45905J			AE	YR318-YR328
2513B	22	X2	AM		3-9	44-21-20	D12391A	K01			D45907J	8			YN501-YR328
2513R	22	X2	AM		0-0	44-21-20	D12391A	J01			D45907J	7			YN501-YR328
2513Z			AM		0-0	44-21-20	D12391A	PERB			D45907J	S/R			YN501-YR328
2514B	22	X2	AN		3-9	44-21-20	D12391A	F01			D45907J	10			YN501-YR328
2514R	22	X2	AN		0-0	44-21-20	D12391A	E01			D45907J	9			YN501-YR328
2514Z			AN		0-0	44-21-20	D12391A	PERB			D45907J	S/R			YN501-YR328
2515B	22	X2	AP		3-9	44-21-20	D12391A	H10			D45907J	12			YN501-YR328
2515R	22	X2	AP		0-0	44-21-20	D12391A	G10			D45907J	11			YN501-YR328
2515Z			AP		0-0	44-21-20	D12391A	PERB			D45907J	S/R			YN501-YR328
2517B	24	M5	AS		2-8	23-11-21	D00623B	B01			D08002J	B01			YD158-YD170
2517R	24	M5	AS		0-0	23-11-21	D00623B	A01			D08002J	A01			YD158-YD170
2517ZI			AS		0-0	23-11-21	D00623B	DED			D08002J	A02			YD158-YD170
2517ZO			AS		0-0	23-11-21	D00623B	PERG	1A		D08002J	PERG	1F		YD158-YD170
2519B	24	Y2	AU		2-7	23-12-41	D00623B	H03			TB0812Y	B009	1A		YD158-YD170
2519R	24	Y2	AU		0-0	23-12-41	D00623B	G03			TB0812Y	A009	1A		YD158-YD170
2519Z			AU		0-0	23-12-41	D00623B	PERG	1A		GB00812	ST..	1A		YD158-YD170
2531B	24	Y2	BR		3-2	23-11-16	D00345A	C03			TB0812Y	B005	1A		YD158-YD170
2531R	24	Y2	BR		0-0	23-11-16	D00345A	B03			TB0812Y	A005	1A		YD158-YD170
2531Z			BR		0-0	23-11-16	D00345A	PERG	1A		GB00812	ST..	1A		YD158-YD170
2532B	24	Y2	BS		3-2	23-11-16	D00345A	D07			TB0812Y	B007	1A		YD158-YD170
2532R	24	Y2	BS		0-0	23-11-16	D00345A	C07			TB0812Y	A007	1A		YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0810

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0811	286A0811				E8-1 ELECTRONIC SHELF (continued)										
2532Z				BS	0-0	23-11-16	D00345A	PERG	1A		GB00812	ST..	1A		YD158-YD170
2533B	24	Y2		BT	4-1	23-11-16	D40075J	A14			TB0812Y	B005	1A		YD158-YD170
2533R	24	Y2		BT	0-0	23-11-16	D40075J	A13			TB0812Y	A005	1A		YD158-YD170
2533Z				BT	0-0	23-11-16	D40075J	PERG	1F		GB00812	ST..	1A		YD158-YD170
2542B	22	X2		BR	4-3	44-21-26	D12391A	D04			D45920J	2			YN501-YR328
2542R	22	X2		BR	0-0	44-21-26	D12391A	C04			D45920J	1			YN501-YR328
2542Z				BR	0-0	44-21-26	D12391A	DED			D45920J			AA	YN501-YR328
2543B	22	X2		BS	4-3	44-21-26	D12391A	D05			D45920J	4			YN501-YR328
2543R	22	X2		BS	0-0	44-21-26	D12391A	C05			D45920J	3			YN501-YR328
2543Z				BS	0-0	44-21-26	D12391A	DED			D45920J			AA	YN501-YR328
2544B	22	X2		BT	4-3	44-21-26	D12391A	D06			D45920J	6			YN501-YR328
2544R	22	X2		BT	0-0	44-21-26	D12391A	C06			D45920J	5			YN501-YR328
2544Z				BT	0-0	44-21-26	D12391A	DED			D45920J			AA	YN501-YR328
2545B	22	X2		BU	4-3	44-21-26	D12391A	D07			D45920J	8			YN501-YR328
2545R	22	X2		BU	0-0	44-21-26	D12391A	C07			D45920J	7			YN501-YR328
2545Z				BU	0-0	44-21-26	D12391A	DED			D45920J			AA	YN501-YR328
2546B	22	X2		BV	4-3	44-21-26	D12391A	D08			D45920J	11			YN501-YR328
2546R	22	X2		BV	0-0	44-21-26	D12391A	C08			D45920J	10			YN501-YR328
2546Z				BV	0-0	44-21-26	D12391A	DED			D45920J			AB	YN501-YR328
2547B	22	X2		BW	4-3	44-21-26	D12391A	D09			D45920J	13			YN501-YR328
2547R	22	X2		BW	0-0	44-21-26	D12391A	C09			D45920J	12			YN501-YR328
2547Z				BW	0-0	44-21-26	D12391A	DED			D45920J			AB	YN501-YR328
2548B	22	X2		BX	4-3	44-21-26	D12391A	D10			D45920J	15			YN501-YR328
2548R	22	X2		BX	0-0	44-21-26	D12391A	C10			D45920J	14			YN501-YR328
2548Z				BX	0-0	44-21-26	D12391A	DED			D45920J			AB	YN501-YR328
2549B	22	X2		BY	4-3	44-21-26	D12391A	D11			D45920J	17			YN501-YR328
2549R	22	X2		BY	0-0	44-21-26	D12391A	C11			D45920J	16			YN501-YR328
2549Z				BY	0-0	44-21-26	D12391A	DED			D45920J			AB	YN501-YR328
2550B	22	X2		BZ	4-3	44-21-26	D12391A	D12			D45920J	20			YN501-YR328
2550R	22	X2		BZ	0-0	44-21-26	D12391A	C12			D45920J	19			YN501-YR328
2550Z				BZ	0-0	44-21-26	D12391A	DED			D45920J			AC	YN501-YR328
2551B	22	X2		CA	4-3	44-21-26	D12391A	D13			D45920J	22			YN501-YR328
2551R	22	X2		CA	0-0	44-21-26	D12391A	C13			D45920J	21			YN501-YR328
2551Z				CA	0-0	44-21-26	D12391A	DED			D45920J			AC	YN501-YR328
2552B	22	X2		CB	4-3	44-21-26	D12391A	D14			D45920J	24			YN501-YR328
2552R	22	X2		CB	0-0	44-21-26	D12391A	C14			D45920J	23			YN501-YR328
2552Z				CB	0-0	44-21-26	D12391A	DED			D45920J			AC	YN501-YR328
2553B	22	X2		CC	4-3	44-21-26	D12391A	D15			D45920J	26			YN501-YR328
2553R	22	X2		CC	0-0	44-21-26	D12391A	C15			D45920J	25			YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0810

Page 8

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0811	286A0811			E8-1 ELECTRONIC SHELF (continued)											
2553Z				CC	0-0	44-21-26	D12391A	DED			D45920J			AC	YN501-YR328
2554B	22	X2		CD	4-3	44-21-26	D12391A	B06			D45920J	29			YN501-YR328
2554R	22	X2		CD	0-0	44-21-26	D12391A	A06			D45920J	28			YN501-YR328
2554Z				CD	0-0	44-21-26	D12391A	DED			D45920J			AD	YN501-YR328
2555B	22	X2		CE	4-3	44-21-26	D12391A	B07			D45920J	31			YN501-YR328
2555R	22	X2		CE	0-0	44-21-26	D12391A	A07			D45920J	30			YN501-YR328
2555Z				CE	0-0	44-21-26	D12391A	DED			D45920J			AD	YN501-YR328
2556B	22	X2		CF	4-3	44-21-26	D12391A	H12			D45920J	33			YN501-YR328
2556R	22	X2		CF	0-0	44-21-26	D12391A	G12			D45920J	32			YN501-YR328
2556Z				CF	0-0	44-21-26	D12391A	DED			D45920J			AD	YN501-YR328
2557B	22	X2		CG	4-3	44-21-26	D12391A	H13			D45920J	35			YN501-YR328
2557R	22	X2		CG	0-0	44-21-26	D12391A	G13			D45920J	34			YN501-YR328
2557Z				CG	0-0	44-21-26	D12391A	DED			D45920J			AD	YN501-YR328
2558B	22	X2		CH	4-3	44-21-26	D12391A	H14			D45920J	42			YN501-YR328
2558R	22	X2		CH	0-0	44-21-26	D12391A	G14			D45920J	41			YN501-YR328
2558Z				CH	0-0	44-21-26	D12391A	DED			D45920J	PERB			YN501-YR328
2559B	22	X2		CI	4-3	44-21-26	D12391A	H15			D45920J	44			YN501-YR328
2559R	22	X2		CI	0-0	44-21-26	D12391A	G15			D45920J	43			YN501-YR328
2559Z				CI	0-0	44-21-26	D12391A	DED			D45920J	PERB			YN501-YR328
2560B	22	X2		CJ	4-3	44-21-26	D12391A	K08			D45920J	46			YN501-YR328
2560R	22	X2		CJ	0-0	44-21-26	D12391A	J08			D45920J	45			YN501-YR328
2560Z				CJ	0-0	44-21-26	D12391A	DED			D45920J	PERB			YN501-YR328
2561B	22	X2		CK	4-3	44-21-26	D12391A	K09			D45920J	48			YN501-YR328
2561R	22	X2		CK	0-0	44-21-26	D12391A	J09			D45920J	47			YN501-YR328
2561Z				CK	0-0	44-21-26	D12391A	DED			D45920J	PERB			YN501-YR328
2562B	22	X2		CL	4-3	44-21-26	D12391A	K07			D45920J	50			YN501-YR328
2562R	22	X2		CL	0-0	44-21-26	D12391A	J07			D45920J	49			YN501-YR328
2562Z				CL	0-0	44-21-26	D12391A	DED			D45920J	PERB			YN501-YR328
2563B	22	X2		CM	4-3	44-21-26	D12391A	K10			D45920J	52			YN501-YR328
2563R	22	X2		CM	0-0	44-21-26	D12391A	J10			D45920J	51			YN501-YR328
2563Z				CM	0-0	44-21-26	D12391A	DED			D45920J	PERB			YN501-YR328
2597B	22	X2		DW	1-9	44-21-26	D45905J	25			D45920J	38			YN501-YR328
2597R	22	X2		DW	0-0	44-21-26	D45905J	26			D45920J	37			YN501-YR328
2597Z				DW	0-0	44-21-26	D45905J	PERB			D45920J	PERB			YN501-YR328
4007B	24	FS		KG	3-8	44-21-12	D12391B	K02			D45167J	A-4			YN501-YR328
4007G	24	FS		KG	0-0	44-21-12	D12391B	K01			D45167J	A-3			YN501-YR328
4007R	24	FS		KG	0-0	44-21-12	D12391B	J02			D45167J	A-2			YN501-YR328
4007Y	24	FS		KG	0-0	44-21-12	D12391B	J01			D45167J	A-1			YN501-YR328
4007Z				KG	0-0	44-21-12	D12391B	PERB			D45167J	= CA			YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W0810

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0811	286A0811				E8-1 ELECTRONIC SHELF (continued)										
4008B	24	FS		KH	3-8	44-21-12	D12391B	K05			D45167J	B-4			YN501-YR328
4008G	24	FS		KH	0-0	44-21-12	D12391B	K04			D45167J	B-3			YN501-YR328
4008R	24	FS		KH	0-0	44-21-12	D12391B	J05			D45167J	B-2			YN501-YR328
4008Y	24	FS		KH	0-0	44-21-12	D12391B	J04			D45167J	B-1			YN501-YR328
4008Z				KH	0-0	44-21-12	D12391B	PERB			D45167J	=CB			YN501-YR328
4011B	24	FS		KK	3-9	44-21-36	D12391A	B02			D45195J	U-4			YN501-YR328
4011G	24	FS		KK	0-0	44-21-36	D12391A	B01			D45195J	U-3			YN501-YR328
4011R	24	FS		KK	0-0	44-21-36	D12391A	A02			D45195J	U-2			YN501-YR328
4011Y	24	FS		KK	0-0	44-21-36	D12391A	A01			D45195J	U-1			YN501-YR328
4011Z				KK	0-0	44-21-36	D12391A	PERB			D45195J	=CU			YN501-YR328
4012B	24	FS		KL	3-10	44-21-46	D12391A	B05			D45199J	U-4			YN501-YR328
4012G	24	FS		KL	0-0	44-21-46	D12391A	B04			D45199J	U-3			YN501-YR328
4012R	24	FS		KL	0-0	44-21-46	D12391A	A05			D45199J	U-2			YN501-YR328
4012Y	24	FS		KL	0-0	44-21-46	D12391A	A04			D45199J	U-1			YN501-YR328
4012Z				KL	0-0	44-21-46	D12391A	PERB			D45199J	=CU			YN501-YR328
4022B	24	FS		KW	3-10	44-21-12	D12391A	F03			D45167J	C-4			YN501-YR328
4022G	24	FS		KW	0-0	44-21-12	D12391A	F02			D45167J	C-3			YN501-YR328
4022R	24	FS		KW	0-0	44-21-12	D12391A	E03			D45167J	C-2			YN501-YR328
4022Y	24	FS		KW	0-0	44-21-12	D12391A	E02			D45167J	C-1			YN501-YR328
4022Z				KW	0-0	44-21-12	D12391A	PERB			D45167J	=CC			YN501-YR328
FRAA					0-0	44-21-26	D45920J		AA		D45920J	9			YN501-YR328
FRAB					0-0	44-21-26	D45920J		AB		D45920J	18			YN501-YR328
FRAC					0-0	44-21-26	D45920J		AC		D45920J	27			YN501-YR328
FRAD					0-0	44-21-26	D45920J		AD		D45920J	36			YN501-YR328
FRAE					0-0	44-21-22	D45905J		AE		D45905J	18			YR318-YR328
W0813	286A0813				E8-1 SHELF										
0001	22	PA			3-0	23-31-06	D10665C	2			D48337J	A03			YC051-YC052
0001	22	PA			2-9	23-31-06	D10665C	2			D48323J	10			YC053-YD157
0002	20	PA			2-0	23-31-06	D10665C	3			GD08101	AC..	1A		YC051-YC052
0002	20	PA			1-5	23-31-06	D10665C	3			GD08105	AC..	1A		YC053-YD157
0003	20	PA			2-0	23-31-06	D10665C	4			GD08101	ST..	1A		YC051-YC052
0003	20	PA			1-5	23-31-06	D10665C	4			GD08105	ST..	1A		YC053-YD157
0004	22	PA			3-0	23-31-06	D10665B	A11			D48337J	A01			YC051-YC052
0004	22	PA			2-8	23-31-06	D10665B	A11			D48337J	A01			YC053-YD157
0005	22	PA			3-0	23-31-06	D10665B	A10			D48337J	B01			YC051-YC052
0005	22	PA			2-8	23-31-06	D10665B	A10			D48337J	B01			YC053-YD157
0006	22	PA			3-0	23-31-06	D10665B	A08			D48337J	A06			YC051-YC052
0006	22	PA			2-8	23-31-06	D10665B	A08			D48337J	A06			YC053-YD157

WIRE LIST

D280A108

91-21-11

Section W0810

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0813		286A0813			E8-1 SHELF (continued)											
0007		22		PA		3-0	23-31-06	D10665B	A09			D48337J	B06			YC051-YC052
0007		22		PA		2-8	23-31-06	D10665B	A09			D48337J	B06			YC053-YD157
0008		22		PA		0-7	SPARE	D48389J	B05			D48389J	A01			YC051-YD157
0008		24		PK		3-5	23-34-01	D45279J	B06			TB0811Y	B001	1A		YD158-YD170
0009		22		PA		0-7	SPARE	D48389J	A05			D48389J	B01			YC051-YD170
0010		20		G5		1-9	23-34-01	TB0811W	A001	1		D48389J	A06			YC051-YC052
0010		20		G5		3-5	23-34-01	TB0811W	A001	1		D48389J	A06			YC053
0010		20		G5		2-10	23-34-01	TB0811W	A001	1		D48323J	12			YC054-YD157
0010		24		PK		2-4	23-34-01	TB0811Y	B001	1A		TB0811Z	A013	1A		YD158-YD170
0011		20		G5		2-0	23-34-01	TB0811W	A001	1		D10527C	2			YC051-YC052
0011		20		G5		1-11	23-34-01	TB0811W	A001	1		D10527C	2			YC053-YD157
0011		20		PA		1-11	23-34-01	TB0811Y	A001	1A		D10527C	2			YD158-YD170
0012		20		G5		1-5	23-34-01	D10527C	4			GD08101	ST..	1A		YC051-YC052
0012		20		G5		1-8	23-34-01	D10527C	4			GD08105	ST..	1A		YC053-YD170
0013		20		PA		1-5	23-34-01	D10527C	3			GD08101	AC..	1A		YC051-YC052
0013		20		PA		1-8	23-34-01	D10527C	3			GD08105	AC..	1A		YC053-YD170
0014		24		PK		1-9	23-34-01	D48389J	A02			TB0811Y	B005	1A		YC051-YC052
0014		24		PK		3-5	23-34-01	D48389J	A02			TB0811Y	B005	1A		YC053-YD170
0015		24		PK		1-6	23-34-01	TB0811W	B001	1		TB0811Y	A005	1A		YC051-YC052
0015		24		PK		1-5	23-34-01	TB0811W	B001	1		TB0811Y	A005	1A		YC053-YD157
0016		24		PK		1-9	23-34-01	D48389J	B02			TB0811Y	B007	1A		YC051-YC052
0016		24		PK		3-5	23-34-01	D48389J	B02			TB0811Y	B007	1A		YC053-YD170
0017		24		PK		0-7	23-34-01	TB0811Y	A005	1A		TB0811Y	A007	1A		YC051-YD170
0018		24		PK		1-9	23-34-01	D48389J	A03			TB0811Y	B009	1A		YC051-YC052
0018		24		PK		3-0	23-34-01	D48389J	A03			TB0811Y	B009	1A		YC053-YD170
0019		24		PK		1-6	23-34-01	TB0811Y	A007	1A		TB0811Y	A009	1A		YC051-YC052
0019		24		PK		2-4	23-34-01	TB0811Y	A007	1A		TB0811Y	A009	1A		YC053-YD170
0020		24		PK		1-9	23-34-01	TB0811W	B001	1		D45279J	B03			YC051-YC052
0020		24		PK		3-5	23-34-01	TB0811W	B001	1		D45279J	B03			YC053-YD157
0020		24		PK		3-0	23-34-01	TB0811Y	A009	1A		D45279J	B03			YD158-YD170
0022		20		G5		2-3	23-34-01	TB0811W	A001	1		D10723	1			YC051-YC052
0022		20		G5		1-10	23-34-01	TB0811W	A001	1		D10723	1			YC053-YD157
0022		20		G5		1-10	23-34-01	TB0811Y	A001	1A		D10723	1			YD158-YD170
0023		20		G5		1-8	23-34-01	D10723	2			GD08101	AC..	1A		YC051-YC052
0023		20		G5		1-11	23-34-01	D10723	2			GD08105	AC..	1A		YC053-YD170
0024		20		PA		1-8	23-34-01	D10723	16			GD08101	ST..	1A		YC051-YC052
0024		20		PA		1-11	23-34-01	D10723	16			GD08105	ST..	1A		YC053-YD170
0025		24		PK		2-3	23-34-01	TB0811W	B001	1		D10723	56			YC051-YC052
0025		24		PK		1-10	23-34-01	TB0811W	B001	1		D10723	56			YC053-YD157

WIRE LIST

D280A108

91-21-11

Section W0810

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice		
W0813	286A0813				E8-1 SHELF (continued)											
0025	24		PK		1-10	23-34-01	TB0811Y	B001	1A			D10723	56			YD158-YD170
0026	20		PA		3-8	23-34-02	D48339J	10				GD08109	ST..	1		YC051-YC052
0026	20		PA		2-6	23-34-02	D48339J	10				GD08106	ST..	1A		YC053-YD157
0026	22		PA		2-7	23-34-02	D10527A	B08				D48339J	7			YD158-YD170
0027	20		PA		1-9	23-34-02	TB0811W	A001	1			D48339J	14			YC051-YC052
0027	20		PA		2-11	23-34-02	TB0811W	A001	1			D48339J	14			YC053-YD157
0027	22		PA		2-7	23-34-02	D10527A	B10				D48339J	14			YD158-YD170
0028	20		G5		3-8	23-34-02	D48339J	15				GD08109	AC..	1		YC051-YC052
0028	20		G5		2-6	23-34-02	D48339J	15				GD08106	AC..	1A		YC053-YD157
0028	22		PA		2-7	23-34-02	D10527A	B12				D48335J	7			YD158-YD170
0029	20		PA		3-8	23-34-02	D48335J	10				GD08109	ST..	1		YC051-YC052
0029	20		PA		2-5	23-34-02	D48335J	10				GD08106	ST..	1A		YC053-YD157
0029	22		PA		2-7	23-34-02	D10527A	B14				D48335J	14			YD158-YD170
0030	20		PA		2-0	23-34-02	D48389J	A04				D48335J	14			YC051-YC052
0030	20		PA		3-10	23-34-02	D48389J	A04				D48335J	14			YC053
0030	20		PA		1-11	23-34-02	D48323J	11				D48335J	14			YC054-YD157
0030	20		G5		3-5	23-34-02	TB0811Y	A001	1A			D48333J	B02			YD158-YD170
0031	20		G5		3-8	23-34-02	D48335J	15				GD08109	AC..	1		YC051-YC052
0031	20		G5		2-5	23-34-02	D48335J	15				GD08106	AC..	1A		YC053-YD157
0032	24		PK		2-1	23-34-01	D10527A	A05				TB0811Y	A011	1A		YC051-YC052
0032	24		PK		1-11	23-34-01	D10527A	A05				TB0811Y	A011	1A		YC053-YC070
0032	24		PK		1-11	23-34-01	D10527A	A05				TB0811Z	A013	1A		YD151-YD157
0032	24		PK		1-11	23-34-01	D10527B	C09				TB0811Z	A013	1A		YD158-YD170
0033	24		PK		1-6	23-34-01	TB0811Y	B011	1A			TB0811W	B001	1		YC051-YC052
0033	24		PK		2-4	23-34-01	TB0811Y	B011	1A			TB0811W	B001	1		YC053-YC070
0033	24		PK		2-4	23-34-01	TB0811Z	B013	1A			TB0811W	B001	1		YD151-YD157
0033	24		PK		2-4	23-34-01	TB0811Z	B013	1A			TB0811Y	A005	1A		YD158-YD170
0034	24		PK		1-9	23-34-01	D48389J	B03				TB0811Y	A011	1A		YC051-YC052
0034	24		PK		3-0	23-34-01	D48389J	B03				TB0811Y	A011	1A		YC053-YC070
0034	24		PK		3-0	23-34-01	D48389J	B03				TB0811Z	A013	1A		YD151-YD170
0035	24		PK		0-7	23-34-01	D10723	10				D10723	11			YC051-YC065
0035	20		PA		0-7	23-34-01	D10723	10				D10723	11			YC067-YD170
0044	24		PK		1-11	23-34-01	TB0811Z	A013	1A			D10527A	B05			YD151-YD157
2501B	24		OT	AA	3-0	23-31-06	D10665B	D02				D48337J	B02			YC051-YC052
2501B	24		OT	AA	2-8	23-31-06	D10665B	D02				D48337J	B02			YC053-YD157
2501W	24		OT	AA	0-0	23-31-06	D10665B	C02				D48337J	A02			YC051-YD157
2501Z				AA	0-0	23-31-06	D10665B	B02				D48337J	PERG	1F		YC051-YD157
2502B	24		Y2	AB	3-0	23-31-06	D10665B	B05				D48337J	B04			YC051-YC052
2502B	24		Y2	AB	2-8	23-31-06	D10665B	B05				D48337J	B04			YC053-YD157

WIRE LIST

D280A108

91-21-11

Section W0810

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0813		286A0813			E8-1 SHELF (continued)											
2502R		24		Y2	AB	0-0	23-31-06	D10665B	A05			D48337J	A04			YC051-YD157
2502Z					AB	0-0	23-31-06	D10665B			AA	D48337J	PERG	1F		YC051-YD157
2503B		24		Y2	AC	3-0	23-31-06	D10665B	B06			D48337J	B05			YC051-YC052
2503B		24		Y2	AC	2-8	23-31-06	D10665B	B06			D48337J	B05			YC053-YD157
2503R		24		Y2	AC	0-0	23-31-06	D10665B	A06			D48337J	A05			YC051-YD157
2503Z					AC	0-0	23-31-06	D10665B			AA	D48337J	PERG	1F		YC051-YD157
2504B		22		X2	AD	2-4	23-34-01	D10527B	D04			D48389J	B07			YC051-YC052
2504B		22		X2	AD	3-0	23-34-01	D10527B	D04			D48389J	B07			YC053-YC070
2504B		22		X2	AD	1-7	23-34-01	SM00003		9		D48389J	B07			YD151-YD157
2504R		22		X2	AD	0-0	23-34-01	D10527B	C04			D48389J	A07			YC051-YC070
2504R		22		X2	AD	0-0	23-34-01	SM00001		9		D48389J	A07			YD151-YD157
2504Z					AD	0-0	23-34-01	D10527B			AC	D48389J			AB	YC051-YC070
2504Z					AD	0-0	23-34-01	SM00REF		3	V	D48389J	A10			YD151-YD157
2505B		22		X2	AE	2-4	23-34-01	D10527B	D05			D48389J	B08			YC051-YC052
2505B		22		X2	AE	3-0	23-34-01	D10527B	D05			D48389J	B08			YC053-YC070
2505B		22		X2	AE	1-11	23-34-01	D10527B	D05			SM00003		9		YD151-YD157
2505R		22		X2	AE	0-0	23-34-01	D10527B	C05			D48389J	A08			YC051-YC070
2505R		22		X2	AE	0-0	23-34-01	D10527B	C05			SM00001		9		YD151-YD157
2505Z					AE	0-0	23-34-01	D10527B			AC	D48389J			AB	YC051-YC070
2505Z					AE	0-0	23-34-01	D10527B			BJ	SM00REF		3	V	YD151-YD157
2506B		24		OT	AF	2-4	23-34-01	D10527B	B14			D45279J	B10			YC051-YC052
2506B		24		OT	AF	3-0	23-34-01	D10527B	B14			D45279J	B10			YC053-YD157
2506W		24		OT	AF	0-0	23-34-01	D10527B	A14			D45279J	A10			YC051-YD157
2506Z					AF	0-0	23-34-01	D10527B	B13			D45279J	A09			YC051-YD157
2507B		22		X2	AG	2-5	23-34-01	D10527A	B06			D45279J	B01			YC051-YC052
2507B		22		X2	AG	3-0	23-34-01	D10527A	B06			D45279J	B01			YC053-YD157
2507B		22		X2	AG	3-0	23-34-01	D10527B	B12			D45279J	B01			YD158-YD170
2507R		22		X2	AG	0-0	23-34-01	D10527A	A06			D45279J	A01			YC051-YD157
2507R		22		X2	AG	0-0	23-34-01	D10527B	A12			D45279J	A01			YD158-YD170
2507Z					AG	0-0	23-34-01	D10527A			AE	D45279J			AD	YC051-YD157
2507Z					AG	0-0	23-34-01	D10527B			AE	D45279J			AD	YD158-YD170
2508B		22		X2	AH	2-5	23-34-01	D10527A	B07			D45279J	B02			YC051-YC052
2508B		22		X2	AH	3-0	23-34-01	D10527A	B07			D45279J	B02			YC053-YD157
2508B		22		X2	AH	3-0	23-34-01	D10527B	D12			D45279J	B02			YD158-YD170
2508R		22		X2	AH	0-0	23-34-01	D10527A	A07			D45279J	A02			YC051-YD157
2508R		22		X2	AH	0-0	23-34-01	D10527B	C12			D45279J	A02			YD158-YD170
2508Z					AH	0-0	23-34-01	D10527A			AE	D45279J			AD	YC051-YD157
2508Z					AH	0-0	23-34-01	D10527B			AE	D45279J			AD	YD158-YD170
2509B		22		X2	AI	2-5	23-34-01	D10527A	B09			D45279J	B04			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W0810

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0813	286A0813				E8-1 SHELF (continued)										
2509B	22	X2	AI		3-0	23-34-01	D10527A	B09			D45279J	B04			YC053-YD157
2509B	22	X2	AI		3-0	23-34-01	D10527B	B13			D45279J	B04			YD158-YD170
2509R	22	X2	AI		0-0	23-34-01	D10527A	A09			D45279J	A04			YC051-YD157
2509R	22	X2	AI		0-0	23-34-01	D10527B	A13			D45279J	A04			YD158-YD170
2509Z			AI		0-0	23-34-01	D10527A			AG	D45279J			AF	YC051-YD157
2509Z			AI		0-0	23-34-01	D10527B			AG	D45279J			AF	YD158-YD170
2510B	22	X2	AJ		2-5	23-34-01	D10527A	B10			D45279J	B05			YC051-YC052
2510B	22	X2	AJ		3-0	23-34-01	D10527A	B10			D45279J	B05			YC053-YD157
2510B	22	X2	AJ		3-0	23-34-01	D10527B	D13			D45279J	B05			YD158-YD170
2510R	22	X2	AJ		0-0	23-34-01	D10527A	A10			D45279J	A05			YC051-YD157
2510R	22	X2	AJ		0-0	23-34-01	D10527B	C13			D45279J	A05			YD158-YD170
2510Z			AJ		0-0	23-34-01	D10527A			AG	D45279J			AF	YC051-YD157
2510Z			AJ		0-0	23-34-01	D10527B			AG	D45279J			AF	YD158-YD170
2511B	22	X2	AK		2-5	23-34-01	D10527A	D06			D45279J	B07			YC051-YC052
2511B	22	X2	AK		3-0	23-34-01	D10527A	D06			D45279J	B07			YC053-YD157
2511B	22	X2	AK		3-0	23-34-01	D10527A	B01			D45279J	B07			YD158-YD170
2511R	22	X2	AK		0-0	23-34-01	D10527A	C06			D45279J	A07			YC051-YD157
2511R	22	X2	AK		0-0	23-34-01	D10527A	A01			D45279J	A07			YD158-YD170
2511Z			AK		0-0	23-34-01	D10527A			AI	D45279J			AH	YC051-YD170
2512B	22	X2	AL		2-5	23-34-01	D10527A	D07			D45279J	B08			YC051-YC052
2512B	22	X2	AL		3-0	23-34-01	D10527A	D07			D45279J	B08			YC053-YD157
2512B	22	X2	AL		3-0	23-34-01	D10527A	D01			D45279J	B08			YD158-YD170
2512R	22	X2	AL		0-0	23-34-01	D10527A	C07			D45279J	A08			YC051-YD157
2512R	22	X2	AL		0-0	23-34-01	D10527A	C01			D45279J	A08			YD158-YD170
2512Z			AL		0-0	23-34-01	D10527A			AI	D45279J			AH	YC051-YD170
2513B	22	X2	AM		1-11	23-34-01	D10527A	D09			D10723	67			YC051-YC052
2513B	22	X2	AM		1-10	23-34-01	D10527A	D09			D10723	67			YC053-YD157
2513B	22	X2	AM		1-9	23-34-01	D10527B	B01			D10723	67			YD158-YD170
2513R	22	X2	AM		0-0	23-34-01	D10527A	C09			D10723	66			YC051-YD157
2513R	22	X2	AM		0-0	23-34-01	D10527B	A01			D10723	66			YD158-YD170
2513Z			AM		0-0	23-34-01	D10527A			AM	D10723	DED			YC051-YD157
2513Z			AM		0-0	23-34-01	D10527B			AM	D10723	DED			YD158-YD170
2514B	22	X2	AN		1-11	23-34-01	D10527A	D10			D10723	63			YC051-YC052
2514B	22	X2	AN		1-10	23-34-01	D10527A	D10			D10723	63			YC053-YD157
2514B	22	X2	AN		1-9	23-34-01	D10527B	D01			D10723	63			YD158-YD170
2514R	22	X2	AN		0-0	23-34-01	D10527A	C10			D10723	62			YC051-YD157
2514R	22	X2	AN		0-0	23-34-01	D10527B	C01			D10723	62			YD158-YD170
2514Z			AN		0-0	23-34-01	D10527A			AM	D10723	DED			YC051-YD157
2514Z			AN		0-0	23-34-01	D10527B			AM	D10723	DED			YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0810

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	Wire No.	GA	CO TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W0813	286A0813				E8-1 SHELF (continued)												
2515B	22		X2	AP	1-11	23-34-01	D10527A	B11				D10723	65			YC051-YC052	
2515B	22		X2	AP	1-10	23-34-01	D10527A	B11				D10723	65			YC053-YD157	
2515B	22		X2	AP	1-9	23-34-01	D10527B	B02				D10723	65			YD158-YD170	
2515R	22		X2	AP	0-0	23-34-01	D10527A	A11				D10723	64			YC051-YD157	
2515R	22		X2	AP	0-0	23-34-01	D10527B	A02				D10723	64			YD158-YD170	
2515Z				AP	0-0	23-34-01	D10527A				AP	D10723	DED			YC051-YD157	
2515Z				AP	0-0	23-34-01	D10527B				AM	D10723	DED			YD158-YD170	
2516B	22		X2	AQ	1-11	23-34-01	D10527A	B12				D10723	61			YC051-YC052	
2516B	22		X2	AQ	1-10	23-34-01	D10527A	B12				D10723	61			YC053-YD157	
2516B	22		X2	AQ	1-9	23-34-01	D10527B	D02				D10723	61			YD158-YD170	
2516R	22		X2	AQ	0-0	23-34-01	D10527A	A12				D10723	60			YC051-YD157	
2516R	22		X2	AQ	0-0	23-34-01	D10527B	C02				D10723	60			YD158-YD170	
2516Z				AQ	0-0	23-34-01	D10527A				AP	D10723	DED			YC051-YD157	
2516Z				AQ	0-0	23-34-01	D10527B				AP	D10723	DED			YD158-YD170	
2517B	22		X2	AR	1-11	23-34-01	D10527A	B14				D10723	54			YC051-YC052	
2517B	22		X2	AR	1-10	23-34-01	D10527A	B14				D10723	54			YC053-YD157	
2517B	22		X2	AR	1-9	23-34-01	D10527B	B03				D10723	54			YD158-YD170	
2517R	22		X2	AR	0-0	23-34-01	D10527A	A14				D10723	53			YC051-YD157	
2517R	22		X2	AR	0-0	23-34-01	D10527B	A03				D10723	53			YD158-YD170	
2517Z				AR	0-0	23-34-01	D10527A				AR	D10723	DED			YC051-YD157	
2517Z				AR	0-0	23-34-01	D10527B				AP	D10723	DED			YD158-YD170	
2518B	22		X2	AS	1-11	23-34-01	D10527A	B15				D10723	50			YC051-YC052	
2518B	22		X2	AS	1-10	23-34-01	D10527A	B15				D10723	50			YC053-YD157	
2518B	22		X2	AS	1-9	23-34-01	D10527B	D03				D10723	50			YD158-YD170	
2518R	22		X2	AS	0-0	23-34-01	D10527A	A15				D10723	49			YC051-YD157	
2518R	22		X2	AS	0-0	23-34-01	D10527B	C03				D10723	49			YD158-YD170	
2518Z				AS	0-0	23-34-01	D10527A				AR	D10723	DED			YC051-YD157	
2518Z				AS	0-0	23-34-01	D10527B				AP	D10723	DED			YD158-YD170	
2519B	22		X2	AT	1-11	23-34-01	D10527A	D11				D10723	52			YC051-YC052	
2519B	22		X2	AT	1-10	23-34-01	D10527A	D11				D10723	52			YC053-YD157	
2519B	22		X2	AT	1-9	23-34-01	D10527B	B04				D10723	52			YD158-YD170	
2519R	22		X2	AT	0-0	23-34-01	D10527A	C11				D10723	51			YC051-YD157	
2519R	22		X2	AT	0-0	23-34-01	D10527B	A04				D10723	51			YD158-YD170	
2519Z				AT	0-0	23-34-01	D10527A				AT	D10723	DED			YC051-YD157	
2519Z				AT	0-0	23-34-01	D10527B				AR	D10723	DED			YD158-YD170	
2520B	22		X2	AU	1-11	23-34-01	D10527A	D12				D10723	48			YC051-YC052	
2520B	22		X2	AU	1-10	23-34-01	D10527A	D12				D10723	48			YC053-YD157	
2520B	22		X2	AU	1-9	23-34-01	D10527B	D04				D10723	48			YD158-YD170	
2520R	22		X2	AU	0-0	23-34-01	D10527A	C12				D10723	47			YC051-YD157	

WIRE LIST

D280A108

91-21-11

Section W0810

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0813	286A0813				E8-1 SHELF (continued)										
2520R	22		X2	AU	0-0	23-34-01	D10527B	C04			D10723	47			YD158-YD170
2520Z				AU	0-0	23-34-01	D10527A			AT	D10723	DED			YC051-YD157
2520Z				AU	0-0	23-34-01	D10527B			AR	D10723	DED			YD158-YD170
2521B	22		X2	AV	1-11	23-34-01	D10527A	D14			D10723	13			YC051-YC052
2521B	22		X2	AV	1-10	23-34-01	D10527A	D14			D10723	13			YC053-YD157
2521B	22		X2	AV	1-9	23-34-01	D10527B	B05			D10723	13			YD158-YD170
2521R	22		X2	AV	0-0	23-34-01	D10527A	C14			D10723	12			YC051-YD157
2521R	22		X2	AV	0-0	23-34-01	D10527B	A05			D10723	12			YD158-YD170
2521Z				AV	0-0	23-34-01	D10527A			AV	D10723	DED			YC051-YD157
2521Z				AV	0-0	23-34-01	D10527B			AR	D10723	DED			YD158-YD170
2522B	22		X2	AW	1-11	23-34-01	D10527A	D15			D10723	38			YC051-YC052
2522B	22		X2	AW	1-10	23-34-01	D10527A	D15			D10723	38			YC053-YD157
2522B	22		X2	AW	1-9	23-34-01	D10527B	D05			D10723	38			YD158-YD170
2522R	22		X2	AW	0-0	23-34-01	D10527A	C15			D10723	37			YC051-YD157
2522R	22		X2	AW	0-0	23-34-01	D10527B	C05			D10723	37			YD158-YD170
2522Z				AW	0-0	23-34-01	D10527A			AV	D10723	DED			YC051-YD157
2522Z				AW	0-0	23-34-01	D10527B			AT	D10723	DED			YD158-YD170
2523B	22		X2	AX	1-10	23-34-01	D10527B	B01			D10723	40			YC051-YC052
2523B	22		X2	AX	1-9	23-34-01	D10527B	B01			D10723	40			YC053-YD157
2523B	22		X2	AX	1-9	23-34-01	D10527B	B06			D10723	40			YD158-YD170
2523R	22		X2	AX	0-0	23-34-01	D10527B	A01			D10723	39			YC051-YD157
2523R	22		X2	AX	0-0	23-34-01	D10527B	A06			D10723	39			YD158-YD170
2523Z				AX	0-0	23-34-01	D10527B			AX	D10723	DED			YC051-YD157
2523Z				AX	0-0	23-34-01	D10527B			AT	D10723	DED			YD158-YD170
2524B	22		X2	AY	1-10	23-34-01	D10527B	B02			D10723	36			YC051-YC052
2524B	22		X2	AY	1-9	23-34-01	D10527B	B02			D10723	36			YC053-YD157
2524B	22		X2	AY	1-9	23-34-01	D10527B	D06			D10723	36			YD158-YD170
2524R	22		X2	AY	0-0	23-34-01	D10527B	A02			D10723	35			YC051-YD157
2524R	22		X2	AY	0-0	23-34-01	D10527B	C06			D10723	35			YD158-YD170
2524Z				AY	0-0	23-34-01	D10527B			AX	D10723	DED			YC051-YD157
2524Z				AY	0-0	23-34-01	D10527B			AT	D10723	DED			YD158-YD170
2525B	22		X2	AZ	1-10	23-34-01	D10527B	B04			D10723	29			YC051-YC052
2525B	22		X2	AZ	1-9	23-34-01	D10527B	B04			D10723	29			YC053-YD157
2525B	22		X2	AZ	1-9	23-34-01	D10527B	B07			D10723	29			YD158-YD170
2525R	22		X2	AZ	0-0	23-34-01	D10527B	A04			D10723	28			YC051-YD157
2525R	22		X2	AZ	0-0	23-34-01	D10527B	A07			D10723	28			YD158-YD170
2525Z				AZ	0-0	23-34-01	D10527B			AZ	D10723	DED			YC051-YD157
2525Z				AZ	0-0	23-34-01	D10527B			AV	D10723	DED			YD158-YD170
2526B	22		X2	BA	1-10	23-34-01	D10527B	B05			D10723	25			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W0810

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	Wire No.	GA	CO TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W0813	286A0813				E8-1 SHELF (continued)											
2526B	22		X2	BA	1-9	23-34-01	D10527B	B05				D10723	25			YC053-YD157
2526B	22		X2	BA	1-9	23-34-01	D10527B	D07				D10723	25			YD158-YD170
2526R	22		X2	BA	0-0	23-34-01	D10527B	A05				D10723	24			YC051-YD157
2526R	22		X2	BA	0-0	23-34-01	D10527B	C07				D10723	24			YD158-YD170
2526Z				BA	0-0	23-34-01	D10527B				AZ	D10723	DED			YC051-YD157
2526Z				BA	0-0	23-34-01	D10527B				AV	D10723	DED			YD158-YD170
2527B	22		X2	BB	1-10	23-34-01	D10527B	D01				D10723	27			YC051-YC052
2527B	22		X2	BB	1-9	23-34-01	D10527B	D01				D10723	27			YC053-YD157
2527B	22		X2	BB	1-9	23-34-01	D10527B	B08				D10723	27			YD158-YD170
2527R	22		X2	BB	0-0	23-34-01	D10527B	C01				D10723	26			YC051-YD157
2527R	22		X2	BB	0-0	23-34-01	D10527B	A08				D10723	26			YD158-YD170
2527Z				BB	0-0	23-34-01	D10527B				BB	D10723	DED			YC051-YD157
2527Z				BB	0-0	23-34-01	D10527B				AX	D10723	DED			YD158-YD170
2528B	22		X2	BC	1-10	23-34-01	D10527B	D02				D10723	23			YC051-YC052
2528B	22		X2	BC	1-9	23-34-01	D10527B	D02				D10723	23			YC053-YD157
2528B	22		X2	BC	1-9	23-34-01	D10527B	D08				D10723	23			YD158-YD170
2528R	22		X2	BC	0-0	23-34-01	D10527B	C02				D10723	22			YC051-YD157
2528R	22		X2	BC	0-0	23-34-01	D10527B	C08				D10723	22			YD158-YD170
2528Z				BC	0-0	23-34-01	D10527B				BB	D10723	DED			YC051-YD157
2528Z				BC	0-0	23-34-01	D10527B				AX	D10723	DED			YD158-YD170
2529B	24		W9	BD	2-5	23-34-02	D10527A	A02				D48339J	5			YC051-YC052
2529B	24		W9	BD	2-7	23-34-02	D10527A	A02				D48339J	5			YC053-YD157
2529B	24		W9	BD	2-7	23-34-02	D10527A	D09				D48339J	4			YD158-YD170
2529W	24		W9	BD	0-0	23-34-02	D10527A	A01				D48339J	4			YC051-YD157
2529W	24		W9	BD	0-0	23-34-02	D10527A	C09				D48339J	3			YD158-YD170
2529Z				BD	0-0	23-34-02	D10527A	A03				D48339J	6			YC051-YD157
2529Z				BD	0-0	23-34-02	D10527A	PERB				D48339J	PERB			YD158-YD170
2530B	24		W9	BE	2-4	23-34-02	D10527B	B09				D48339J	2			YC051-YC052
2530B	24		W9	BE	2-6	23-34-02	D10527B	B09				D48339J	2			YC053-YD157
2530B	22		X2	BE	2-7	23-34-02	D10527A	A08				D48339J	6			YD158-YD170
2530R	22		X2	BE	0-0	23-34-02	D10527A	A09				D48339J	5			YD158-YD170
2530W	24		W9	BE	0-0	23-34-02	D10527B	A09				D48339J	1			YC051-YD157
2530Z				BE	0-0	23-34-02	D10527B				BE	D48339J			BF	YC051-YD157
2530Z				BE	0-0	23-34-02	D10527A	PERB				D48339J	PERB			YD158-YD170
2531B	24		W9	BF	2-4	23-34-02	D10527B	B10				D48339J	8			YC051-YC052
2531B	24		W9	BF	2-6	23-34-02	D10527B	B10				D48339J	8			YC053-YD157
2531B	24		W9	BF	2-7	23-34-02	D10527A	D10				D48339J	9			YD158-YD170
2531W	24		W9	BF	0-0	23-34-02	D10527B	A10				D48339J	7			YC051-YD157
2531W	24		W9	BF	0-0	23-34-02	D10527A	C10				D48339J	8			YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0810

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W0813	286A0813	E8-1 SHELF (continued)													
2531Z		BF	0-0	23-34-02	D10527B			BE	D48339J			BF	YC051-YD157		
2531Z		BF	0-0	23-34-02	D10527A	PERB			D48339J	PERB			YD158-YD170		
2532B	24	W9	BG	2-4	23-34-02	D10527B	D09		D48335J	2			YC051-YC052		
2532B	24	W9	BG	2-5	23-34-02	D10527B	D09		D48335J	2			YC053-YD157		
2532B	24	W9	BG	2-7	23-34-02	D10527A	D11		D48339J	11			YD158-YD170		
2532W	24	W9	BG	0-0	23-34-02	D10527B	C09		D48335J	1			YC051-YD157		
2532W	24	W9	BG	0-0	23-34-02	D10527A	C11		D48339J	10			YD158-YD170		
2532Z		BG	0-0	23-34-02	D10527B			BG	D48335J			BH	YC051-YD157		
2532Z		BG	0-0	23-34-02	D10527A	PERB			D48339J	PERB			YD158-YD170		
2533B	24	W9	BH	2-4	23-34-02	D10527B	D10		D48335J	8			YC051-YC052		
2533B	24	W9	BH	2-5	23-34-02	D10527B	D10		D48335J	8			YC053-YD157		
2533B	22	X2	BH	2-7	23-34-02	D10527A	A11		D48339J	13			YD158-YD170		
2533R	22	X2	BH	0-0	23-34-02	D10527A	A10		D48339J	12			YD158-YD170		
2533W	24	W9	BH	0-0	23-34-02	D10527B	C10		D48335J	7			YC051-YD157		
2533Z		BH	0-0	23-34-02	D10527B			BG	D48335J			BH	YC051-YD157		
2533Z		BH	0-0	23-34-02	D10527A	PERB			D48339J	PERB			YD158-YD170		
2534B	24	W9	BI	2-5	23-34-02	D10527A	B02		D48335J	5			YC051-YD157		
2534W	24	W9	BI	0-0	23-34-02	D10527A	B01		D48335J	4			YC051-YD157		
2534Z		BI	0-0	23-34-02	D10527A	B03			D48335J	6			YC051-YD157		
2535B	22	X2	BJ	1-11	23-34-01	SM00003	9		D10527B	D04			YD151-YD157		
2535B	22	X2	BJ	3-0	23-34-01	D48389J	B07		D10527B	B09			YD158-YD170		
2535R	22	X2	BJ	0-0	23-34-01	SM00001	9		D10527B	C04			YD151-YD157		
2535R	22	X2	BJ	0-0	23-34-01	D48389J	A07		D10527B	A09			YD158-YD170		
2535Z		BJ	0-0	23-34-01	SM00REF	3	V		D10527B			BJ	YD151-YD157		
2535Z		BJ	0-0	23-34-01	D48389J	A10			D10527B	PERB			YD158-YD170		
2536B	22	X2	BK	1-8	23-32-12	D48389J	B04		D45279J	B11			YD158-YD170		
2536R	22	X2	BK	0-0	23-32-12	D48389J	A04		D45279J	A11			YD158-YD170		
2536Z		BK	0-0	23-32-12	D48389J	B05			D45279J	A12			YD158-YD170		
2537B	24	W9	BL	2-7	23-34-02	D10527A	D08		D48339J	2			YD158-YD170		
2537W	24	W9	BL	0-0	23-34-02	D10527A	C08		D48339J	1			YD158-YD170		
2537Z		BL	0-0	23-34-02	D10527A	PERB			D48339J	PERB			YD158-YD170		
2538B	24	W9	BM	2-7	23-34-02	D10527A	D12		D48335J	2			YD158-YD170		
2538W	24	W9	BM	0-0	23-34-02	D10527A	C12		D48335J	1			YD158-YD170		
2538Z		BM	0-0	23-34-02	D10527A	PERB			D48335J	PERB			YD158-YD170		
2539B	24	W9	BN	2-7	23-34-02	D10527A	D13		D48335J	4			YD158-YD170		
2539W	24	W9	BN	0-0	23-34-02	D10527A	C13		D48335J	3			YD158-YD170		
2539Z		BN	0-0	23-34-02	D10527A	PERB			D48335J	PERB			YD158-YD170		
2540B	22	X2	BP	2-7	23-34-02	D10527A	A12		D48335J	6			YD158-YD170		
2540R	22	X2	BP	0-0	23-34-02	D10527A	A13		D48335J	5			YD158-YD170		

WIRE LIST

D280A108

91-21-11

Section W0810

Page 18

Nov 12/2012

Bundle No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	Wire No.	GA	CO TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W0813	286A0813			E8-1 SHELF (continued)												
2540Z				BP	0-0	23-34-02	D10527A	PERB				D48335J	PERB			YD158-YD170
2541B	24		W9	BQ	2-7	23-34-02	D10527A	D14				D48335J	9			YD158-YD170
2541W	24		W9	BQ	0-0	23-34-02	D10527A	C14				D48335J	8			YD158-YD170
2541Z				BQ	0-0	23-34-02	D10527A	PERB				D48335J	PERB			YD158-YD170
2542B	24		W9	BR	2-7	23-34-02	D10527A	D15				D48335J	11			YD158-YD170
2542W	24		W9	BR	0-0	23-34-02	D10527A	C15				D48335J	10			YD158-YD170
2542Z				BR	0-0	23-34-02	D10527A	PERB				D48335J	PERB			YD158-YD170
2543B	22		X2	BS	2-7	23-34-02	D10527A	A15				D48335J	13			YD158-YD170
2543R	22		X2	BS	0-0	23-34-02	D10527A	A14				D48335J	12			YD158-YD170
2543Z				BS	0-0	23-34-02	D10527A	PERB				D48335J	PERB			YD158-YD170
3001B	24		PM	GA	3-0	23-34-01	D45279J	B10				D10527B	D10			YD158-YD170
3001R	24		PM	GA	0-0	23-34-01	D45279J	A10				D10527B	D09			YD158-YD170
3001Y	24		PM	GA	0-0	23-34-01	D45279J	B09				D10527B	D11			YD158-YD170
3501B	22		X3	HA	3-0	23-34-02	D10527A	B07				D48333J	B01			YD158-YD170
3501R	22		X3	HA	0-0	23-34-02	D10527A	A07				D48333J	A01			YD158-YD170
3501Y	22		X3	HA	0-0	23-34-02	D10527A	C07				D48333J	A02			YD158-YD170
3501Z				HA	0-0	23-34-02	D10527A	PERB				D48333J	PERG	1F		YD158-YD170
FRAA					0-0	23-31-06	D10665B			AA		D10665B	D13			YC051-YD157
FRAB					0-0	23-34-01	D48389J			AB		D48389J	A10			YC051-YC070
FRAC					0-0	23-34-01	D10527B			AC		D10527B	D03			YC051-YC070
FRAD					0-0	23-34-01	D45279J	A03				D45279J			AD	YC051-YD170
FRAE					0-0	23-34-01	D10527A	A08				D10527A			AE	YC051-YD157
FRAE					0-0	23-34-01	D10527B	PERB				D10527B			AE	YD158-YD170
FRAF					0-0	23-34-01	D45279J			AF		D45279J	A06			YC051-YD170
FRAG					0-0	23-34-01	D10527A			AG		D10527A	B08			YC051-YD157
FRAG					0-0	23-34-01	D10527B			AG		D10527B	PERB			YD158-YD170
FRAH					0-0	23-34-01	D45279J			AH		D45279J	B09			YC051-YD157
FRAH					0-0	23-34-01	D45279J			AH		D45279J	A09			YD158-YD170
FRAI					0-0	23-34-01	D10527A			AI		D10527A	C08			YC051-YD157
FRAI					0-0	23-34-01	D10527A			AI		D10527A	PERB			YD158-YD170
FRAM					0-0	23-34-01	D10527A			AM		D10527A	D08			YC051-YD157
FRAM					0-0	23-34-01	D10527B			AM		D10527B	PERB			YD158-YD170
FRAP					0-0	23-34-01	D10527A			AP		D10527A	A13			YC051-YD157
FRAP					0-0	23-34-01	D10527B			AP		D10527B	PERB			YD158-YD170
FRAR					0-0	23-34-01	D10527A			AR		D10527A	B13			YC051-YD157
FRAR					0-0	23-34-01	D10527B			AR		D10527B	PERB			YD158-YD170
FRAT					0-0	23-34-01	D10527A			AT		D10527A	C13			YC051-YD157
FRAT					0-0	23-34-01	D10527B			AT		D10527B	PERB			YD158-YD170
FRAV					0-0	23-34-01	D10527A			AV		D10527A	D13			YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W0810

Page 19

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W0813		286A0813			E8-1 SHELF (continued)											
	FRAV					0-0	23-34-01	D10527B				AV	D10527B	PERB		YD158-YD170
	FRAX					0-0	23-34-01	D10527B				AX	D10527B	A03		YC051-YD157
	FRAX					0-0	23-34-01	D10527B				AX	D10527B	PERB		YD158-YD170
	FRAZ					0-0	23-34-01	D10527B				AZ	D10527B	B03		YC051-YD157
	FRBB					0-0	23-34-01	D10527B				BB	D10527B	C03		YC051-YD157
	FRBE					0-0	23-34-02	D10527B				BE	D10527B	A08		YC051-YD157
	FRBF					0-0	23-34-02	D48339J				BF	D48339J	3		YC051-YD157
	FRBG					0-0	23-34-02	D10527B				BG	D10527B	C08		YC051-YD157
	FRBH					0-0	23-34-02	D48335J				BH	D48335J	3		YC051-YD157
	FRBJ					0-0	23-34-01	D10527B				BJ	D10527B	D03		YD151-YD157
	YAAA					0-0	23-34-02	D10527A	PERG	1F			D48339J	PERB		YC051-YC052
	YAAA					0-0	23-34-02	D10527A	PERG	1A			D48339J	PERB		YC053-YD157
	YAAA					0-0	23-34-02	D10527A	PERB				OAS0001			YD158-YD170
	YAAB					0-0	23-34-02	D10527B	PERG	1F			D48335J	PERB		YC051-YC052
	YAAB					0-0	23-34-02	D10527B	PERG	1A			D48335J	PERB		YC053-YD157
	YAAB					0-0	23-34-02	D48335J	PERB				OAS0001			YD158-YD170
	YAAC					0-0	23-34-02	D48339J	PERB				OAS0001			YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W0810

Page 20 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1022 286A1022 L WING TRAILING EDGE:DISC BRACKET STA 254L TO W/W DISC & AFT CARGO DISC																
1001	20	HP		AA		16-8	28-21-11	D40024J	34			D42104P	25			YC051-YC052
1001	20	HP		AA		16-6	28-21-11	D40024P	34			D42104P	25			YC053-YC057
1001	20	HP		AA		16-7	28-21-11	D40024P	34			D42104P	25			YC058-YD152
1001	20	HP		AA		16-5	28-21-11	D40024P	34			D42104P	25			YD153-YN236, YN501-YR328
1001Z				AA		0-0	28-21-11	D40024J	S/R			D42104P	S/R			YC051-YC052
1001Z				AA		0-0	28-21-11	D40024P	S/R			D42104P	S/R			YC053-YN236, YN501-YR328
1002	18	HP		AB		3-11	27-53-21	D11818	8			GD00224	ST..	E	*1	YC051-YC052
1002	18	HP		AB		4-0	27-53-21	D11818	8			GD00224	ST..	E	*1	YC053-YD152
1002	18	HP		AB		4-1	27-53-21	D11818	8			GD00224	ST..	E	*1	YD153-YN236, YN501-YR328
1002Z				AB		0-0	27-53-21	D11818	S/R			GD00224	ST..	E	*1	YC051-YN236, YN501-YR328
1003	18	HP		AC		4-6	27-53-21	D11820	8			GD00226	ST..	E	*2	YC051-YC052
1003	18	HP		AC		4-7	27-53-21	D11820	8			GD00226	ST..	E	*2	YC053-YC057
1003	18	HP		AC		4-3	27-53-21	D11820	8			GD00226	ST..	E	*2	YC058-YD152
1003	18	HP		AC		4-5	27-53-21	D11820	8			GD00226	ST..	E	*2	YD153-YN236, YN501-YR328
1003Z				AC		0-0	27-53-21	D11820	S/R			GD00226	ST..	E	*2	YC051-YN236, YN501-YR328
2001B	20	Y6		GA		16-1	27-18-11	D40024J	7			D42100P	2			YC051-YC052
2001B	20	Y6		GA		15-11	27-18-11	D40024P	7			D42100P	2			YC053-YD152
2001B	20	Y6		GA		15-9	27-18-11	D40024P	7			D42100P	2			YD153-YN236, YN501-YR328
2001R	20	Y6		GA		0-0	27-18-11	D40024J	6			D42100P	1			YC051-YC052
2001R	20	Y6		GA		0-0	27-18-11	D40024P	6			D42100P	1			YC053-YN236, YN501-YR328
2001Z				GA		0-0	27-18-11	D40024J	S/R			D42100P	S/R			YC051-YC052
2001Z				GA		0-0	27-18-11	D40024P	S/R			D42100P	S/R			YC053-YN236, YN501-YR328
2002B	20	Y6		GB		16-1	22-11-31	D40024J	2			D42100P	4			YC051-YC052
2002B	20	Y6		GB		15-11	22-11-31	D40024P	2			D42100P	4			YC053-YD152
2002B	20	Y6		GB		15-9	22-11-31	D40024P	2			D42100P	4			YD153-YN236, YN501-YR328
2002R	20	Y6		GB		0-0	22-11-31	D40024J	1			D42100P	3			YC051-YC052
2002R	20	Y6		GB		0-0	22-11-31	D40024P	1			D42100P	3			YC053-YN236, YN501-YR328
2002Z				GB		0-0	22-11-31	D40024J	S/R			D42100P	S/R			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W1020

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1022	286A1022			L WING TRAILING EDGE: DISC BRACKET STA 254L TO W/W DISC & AFT CARGO DISC (continued)											
2002Z				GB	0-0	22-11-31	D40024P		S/R		D42100P		S/R		YC053-YN236, YN501-YR328
2003B	20	Y6	GC		16-0	22-11-31	D40024J	20			D42102P	2			YC051-YC052
2003B	20	Y6	GC		15-10	22-11-31	D40024P	20			D42102P	2			YC053-YC057
2003B	20	Y6	GC		15-11	22-11-31	D40024P	20			D42102P	2			YC058-YD152
2003B	20	Y6	GC		15-9	22-11-31	D40024P	20			D42102P	2			YD153-YN236, YN501-YR328
2003R	20	Y6	GC		0-0	22-11-31	D40024J	19			D42102P	1			YC051-YC052
2003R	20	Y6	GC		0-0	22-11-31	D40024P	19			D42102P	1			YC053-YN236, YN501-YR328
2003Z			GC		0-0	22-11-31	D40024J		S/R		D42102P		S/R		YC051-YC052
2003Z			GC		0-0	22-11-31	D40024P		S/R		D42102P		S/R		YC053-YN236, YN501-YR328
2004B	20	Y6	GD		16-1	27-32-21	D40024J	30			D42100P	21			YC051-YC052
2004B	20	Y6	GD		15-11	27-32-21	D40024P	30			D42100P	21			YC053-YD152
2004B	20	Y6	GD		15-9	27-32-21	D40024P	30			D42100P	21			YD153-YN236, YN501-YR328
2004R	20	Y6	GD		0-0	27-32-21	D40024J	29			D42100P	20			YC051-YC052
2004R	20	Y6	GD		0-0	27-32-21	D40024P	29			D42100P	20			YC053-YN236, YN501-YR328
2004Z			GD		0-0	27-32-21	D40024J		S/R		D42100P		S/R		YC051-YC052
2004Z			GD		0-0	27-32-21	D40024P		S/R		D42100P		S/R		YC053-YN236, YN501-YR328
2005B	20	Y6	GE		16-0	22-11-11	D40024J	25			D42102P	4			YC051-YC052
2005B	20	Y6	GE		15-10	22-11-11	D40024P	25			D42102P	4			YC053-YC057
2005B	20	Y6	GE		15-11	22-11-11	D40024P	25			D42102P	4			YC058-YD152
2005B	20	Y6	GE		15-9	22-11-11	D40024P	25			D42102P	4			YD153-YN236, YN501-YR328
2005R	20	Y6	GE		0-0	22-11-11	D40024J	24			D42102P	3			YC051-YC052
2005R	20	Y6	GE		0-0	22-11-11	D40024P	24			D42102P	3			YC053-YN236, YN501-YR328
2005Z			GE		0-0	22-11-11	D40024J		S/R		D42102P		S/R		YC051-YC052
2005Z			GE		0-0	22-11-11	D40024P		S/R		D42102P		S/R		YC053-YN236, YN501-YR328
2006B	20	M2	GF		16-8	27-52-11	D40024J	37			D42104P	2			YC051-YC052
2006B	20	M2	GF		16-6	27-52-11	D40024P	37			D42104P	2			YC053-YC057
2006B	20	M2	GF		16-7	27-52-11	D40024P	37			D42104P	2			YC058-YD152
2006B	20	M2	GF		16-5	27-52-11	D40024P	37			D42104P	2			YD153-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W1020

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice
W1022	286A1022				L WING TRAILNG EDGE:DISC BRACKET STA 254L TO W/W DISC & AFT CARGO DISC (continued)										
2006R	20	M2	GF		0-0	27-52-11	D40024J	36				D42104P	1		YC051-YC052
2006R	20	M2	GF		0-0	27-52-11	D40024P	36				D42104P	1		YC053-YN236, YN501-YR328
2006ZI			GF		0-0	27-52-11	D40024J	38				D42104P	3		YC051-YC052
2006ZI			GF		0-0	27-52-11	D40024P	38	18			D42104P	3		YC053-YN236, YN501-YR328
2006ZO			GF		0-0	27-52-11	D40024J	S/R				D42104P	S/R		YC051-YC052
2006ZO			GF		0-0	27-52-11	D40024P	S/R				D42104P	S/R		YC053-YN236, YN501-YR328
2007B	20	M2	GG		16-8	27-52-11	D40024J	41				D42104P	5		YC051-YC052
2007B	20	M2	GG		16-6	27-52-11	D40024P	41				D42104P	5		YC053-YC057
2007B	20	M2	GG		16-7	27-52-11	D40024P	41				D42104P	5		YC058-YD152
2007B	20	M2	GG		16-5	27-52-11	D40024P	41				D42104P	5		YD153-YN236, YN501-YR328
2007R	20	M2	GG		0-0	27-52-11	D40024J	40				D42104P	4		YC051-YC052
2007R	20	M2	GG		0-0	27-52-11	D40024P	40				D42104P	4		YC053-YN236, YN501-YR328
2007ZI			GG		0-0	27-52-11	D40024J	39				D42104P	6		YC051-YC052
2007ZI			GG		0-0	27-52-11	D40024P	39	18			D42104P	6		YC053-YN236, YN501-YR328
2007ZO			GG		0-0	27-52-11	D40024J	S/R				D42104P	S/R		YC051-YC052
2007ZO			GG		0-0	27-52-11	D40024P	S/R				D42104P	S/R		YC053-YN236, YN501-YR328
2008B	20	Y6	GI		11-11	27-53-21	D11818	1				D11820	7		YC051-YC052
2008B	20	Y6	GI		12-1	27-53-21	D11818	1				D11820	7		YC053-YC057
2008B	20	Y6	GI		13-0	27-53-21	D11818	1				D11820	7		YC058-YN236, YN501-YR328
2008R	20	Y6	GI		0-0	27-53-21	D11818	2				D11820	6		YC051-YN236, YN501-YR328
2008Z			GI		0-0	27-53-21	D11818	S/R				D11820	S/R		YC051-YN236, YN501-YR328
2009B	20	Y6	GH		4-4	27-53-21	D11818	7				D40024J	12		YC051-YC052
2009B	20	Y6	GH		4-3	27-53-21	D11818	7				D40024P	12		YC053-YN236, YN501-YR328
2009R	20	Y6	GH		0-0	27-53-21	D11818	6				D40024J	11		YC051-YC052
2009R	20	Y6	GH		0-0	27-53-21	D11818	6				D40024P	11		YC053-YN236, YN501-YR328
2009Z			GH		0-0	27-53-21	D11818	S/R				D40024J	S/R		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W1020

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1022	286A1022			L WING TRAILNG EDGE:DISC BRACKET STA 254L TO W/W DISC & AFT CARGO DISC (continued)											
2009Z				GH	0-0	27-53-21	D11818		S/R		D40024P		S/R		YC053-YN236, YN501-YR328
2010B	20	Y6	GJ		7-0	27-53-21	D11820		1		D42104P		8		YC051-YC052
2010B	20	Y6	GJ		7-1	27-53-21	D11820		1		D42104P		8		YC053-YC057
2010B	20	Y6	GJ		6-9	27-53-21	D11820		1		D42104P		8		YC058-YD152
2010B	20	Y6	GJ		6-10	27-53-21	D11820		1		D42104P		8		YD153-YN236, YN501-YR328
2010R	20	Y6	GJ		0-0	27-53-21	D11820		2		D42104P		7		YC051-YN236, YN501-YR328
2010Z				GJ	0-0	27-53-21	D11820		S/R		D42104P		S/R		YC051-YN236, YN501-YR328
2011B	20	Y6	GK		16-1	27-62-14	D40024J		43		D42100P		12		YC051-YC052
2011B	20	Y6	GK		15-11	27-62-14	D40024P		43		D42100P		12		YC053-YD152
2011B	20	Y6	GK		15-9	27-62-14	D40024P		43		D42100P		12		YD153-YN236, YN501-YR328
2011R	20	Y6	GK		0-0	27-62-14	D40024J		42		D42100P		11		YC051-YC052
2011R	20	Y6	GK		0-0	27-62-14	D40024P		42		D42100P		11		YC053-YN236, YN501-YR328
2011Z				GK	0-0	27-62-14	D40024J		S/R		D42100P		S/R		YC051-YC052
2011Z				GK	0-0	27-62-14	D40024P		S/R		D42100P		S/R		YC053-YN236, YN501-YR328
2012B	20	Y6	OL		15-9	27-62-11	D40024P		48		D42100P		30		YL953-YL999, YR301-YR328
2012R	20	Y6	OL		0-0	27-62-11	D40024P		47		D42100P		29		YL953-YL999, YR301-YR328
2012Z				OL	0-0	27-62-11	D40024P		S/R		D42100P		S/R		YL953-YL999, YR301-YR328
2013B	20	Y6	OM		15-9	27-62-11	D40024P		50		D42100P		32		YL953-YL999, YR301-YR328
2013R	20	Y6	OM		0-0	27-62-11	D40024P		49		D42100P		31		YL953-YL999, YR301-YR328
2013Z				OM	0-0	27-62-11	D40024P		S/R		D42100P		S/R		YL953-YL999, YR301-YR328
2014B	20	Y6	ON		15-9	27-62-11	D40024P		52		D42100P		34		YL953-YL999, YR301-YR328
2014R	20	Y6	ON		0-0	27-62-11	D40024P		51		D42100P		33		YL953-YL999, YR301-YR328
2014Z				ON	0-0	27-62-11	D40024P		S/R		D42100P		S/R		YL953-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W1020

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To							
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1022	286A1022			L WING TRAILNG EDGE:DISC BRACKET STA 254L TO W/W DISC & AFT CARGO DISC (continued)											
2015B	20	Y6	OP		15-9	27-62-11	D40024P	54			D42100P	36			YL953-YL999, YR301-YR328
2015R	20	Y6	OP		0-0	27-62-11	D40024P	53			D42100P	35			YL953-YL999, YR301-YR328
2015Z			OP		0-0	27-62-11	D40024P	S/R			D42100P	S/R			YL953-YL999, YR301-YR328
3001B	20	Y7	WA		16-1	27-18-11	D40024J	9			D42100P	6			YC051-YC052
3001B	20	Y7	WA		15-11	27-18-11	D40024P	9			D42100P	6			YC053-YD152
3001B	20	Y7	WA		15-9	27-18-11	D40024P	9			D42100P	6			YD153-YN236, YN501-YR328
3001R	20	Y7	WA		0-0	27-18-11	D40024J	8			D42100P	5			YC051-YC052
3001R	20	Y7	WA		0-0	27-18-11	D40024P	8			D42100P	5			YC053-YN236, YN501-YR328
3001Y	20	Y7	WA		0-0	27-18-11	D40024J	10			D42100P	7			YC051-YC052
3001Y	20	Y7	WA		0-0	27-18-11	D40024P	10			D42100P	7			YC053-YN236, YN501-YR328
3001Z			WA		0-0	27-18-11	D40024J	S/R			D42100P	S/R			YC051-YC052
3001Z			WA		0-0	27-18-11	D40024P	S/R			D42100P	S/R			YC053-YN236, YN501-YR328
3002B	20	Y7	WB		16-1	22-11-31	D40024J	4			D42100P	9			YC051-YC052
3002B	20	Y7	WB		15-11	22-11-31	D40024P	4			D42100P	9			YC053-YD152
3002B	20	Y7	WB		15-9	22-11-31	D40024P	4			D42100P	9			YD153-YN236, YN501-YR314
3002B	20	Y6	WB		15-9	22-11-31	D40024P	4			D42100P	9			YR315-YR328
3002R	20	Y7	WB		0-0	22-11-31	D40024J	3			D42100P	8			YC051-YC052
3002R	20	Y7	WB		0-0	22-11-31	D40024P	3			D42100P	8			YC053-YN236, YN501-YR314
3002R	20	Y6	WB		0-0	22-11-31	D40024P	3			D42100P	8			YR315-YR328
3002Y	20	Y7	WB		0-0	22-11-31	D40024J	5			D42100P	10			YC051-YC052
3002Y	20	Y7	WB		0-0	22-11-31	D40024P	5			D42100P	10			YC053-YN236, YN501-YR314
3002Z			WB		0-0	22-11-31	D40024J	S/R			D42100P	S/R			YC051-YC052
3002Z			WB		0-0	22-11-31	D40024P	S/R			D42100P	S/R			YC053-YN236, YN501-YR328
3003B	20	Y7	WC		16-0	22-11-31	D40024J	22			D42102P	6			YC051-YC052
3003B	20	Y7	WC		15-10	22-11-31	D40024P	22			D42102P	6			YC053-YC057
3003B	20	Y7	WC		15-11	22-11-31	D40024P	22			D42102P	6			YC058-YD152
3003B	20	Y7	WC		15-9	22-11-31	D40024P	22			D42102P	6			YD153-YN236, YN501-YR314

WIRE LIST

D280A108

91-21-11

Section W1020

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1022	286A1022				L WING TRAILNG EDGE:DISC BRACKET STA 254L TO W/W DISC & AFT CARGO DISC (continued)										
3003B	20		Y6	WC	15-9	22-11-31	D40024P	22			D42102P	6			YR315-YR328
3003R	20		Y7	WC	0-0	22-11-31	D40024J	21			D42102P	5			YC051-YC052
3003R	20		Y7	WC	0-0	22-11-31	D40024P	21			D42102P	5			YC053-YN236, YN501-YR314
3003R	20		Y6	WC	0-0	22-11-31	D40024P	21			D42102P	5			YR315-YR328
3003Y	20		Y7	WC	0-0	22-11-31	D40024J	23			D42102P	7			YC051-YC052
3003Y	20		Y7	WC	0-0	22-11-31	D40024P	23			D42102P	7			YC053-YN236, YN501-YR314
3003Z				WC	0-0	22-11-31	D40024J	S/R			D42102P	S/R			YC051-YC052
3003Z				WC	0-0	22-11-31	D40024P	S/R			D42102P	S/R			YC053-YN236, YN501-YR328
3004B	20		Y7	WD	16-1	27-32-21	D40024J	32			D42100P	25			YC051-YC052
3004B	20		Y7	WD	15-11	27-32-21	D40024P	32			D42100P	25			YC053-YD152
3004B	20		Y7	WD	15-9	27-32-21	D40024P	32			D42100P	25			YD153-YN236, YN501-YR328
3004R	20		Y7	WD	0-0	27-32-21	D40024J	31			D42100P	24			YC051-YC052
3004R	20		Y7	WD	0-0	27-32-21	D40024P	31			D42100P	24			YC053-YN236, YN501-YR328
3004Y	20		Y7	WD	0-0	27-32-21	D40024J	33			D42100P	26			YC051-YC052
3004Y	20		Y7	WD	0-0	27-32-21	D40024P	33			D42100P	26			YC053-YN236, YN501-YR328
3004Z				WD	0-0	27-32-21	D40024J	S/R			D42100P	S/R			YC051-YC052
3004Z				WD	0-0	27-32-21	D40024P	S/R			D42100P	S/R			YC053-YN236, YN501-YR328
3005B	20		Y7	WE	16-0	22-12-31	D40024J	27			D42102P	9			YC051-YC052
3005B	20		Y7	WE	15-10	22-12-31	D40024P	27			D42102P	9			YC053-YC057
3005B	20		Y7	WE	15-11	22-12-31	D40024P	27			D42102P	9			YC058-YD152
3005B	20		Y7	WE	15-9	22-12-31	D40024P	27			D42102P	9			YD153-YN236, YN501-YR328
3005R	20		Y7	WE	0-0	22-12-31	D40024J	26			D42102P	8			YC051-YC052
3005R	20		Y7	WE	0-0	22-12-31	D40024P	26			D42102P	8			YC053-YN236, YN501-YR328
3005Y	20		Y7	WE	0-0	22-12-31	D40024J	28			D42102P	10			YC051-YC052
3005Y	20		Y7	WE	0-0	22-12-31	D40024P	28			D42102P	10			YC053-YN236, YN501-YR328
3005Z				WE	0-0	22-12-31	D40024J	S/R			D42102P	S/R			YC051-YC052
3005Z				WE	0-0	22-12-31	D40024P	S/R			D42102P	S/R			YC053-YN236, YN501-YR328
3006B	20		Y7	WF	16-8	27-53-21	D40024J	17			D42104P	10			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W1020

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1022	286A1022			L WING TRAILING EDGE:DISC BRACKET STA 254L TO W/W DISC & AFT CARGO DISC (continued)											
3006B	20	Y7	WF		16-6	27-53-21	D40024P	17			D42104P	10			YC053-YC057
3006B	20	Y7	WF		16-7	27-53-21	D40024P	17			D42104P	10			YC058-YD152
3006B	20	Y7	WF		16-5	27-53-21	D40024P	17			D42104P	10			YD153-YN236, YN501-YR328
3006R	20	Y7	WF		0-0	27-53-21	D40024J	16			D42104P	9			YC051-YC052
3006R	20	Y7	WF		0-0	27-53-21	D40024P	16			D42104P	9			YC053-YN236, YN501-YR328
3006Y	20	Y7	WF		0-0	27-53-21	D40024J	18			D42104P	11			YC051-YC052
3006Y	20	Y7	WF		0-0	27-53-21	D40024P	18			D42104P	11			YC053-YN236, YN501-YR328
3006Z			WF		0-0	27-53-21	D40024J	S/R			D42104P	S/R			YC051-YC052
3006Z			WF		0-0	27-53-21	D40024P	S/R			D42104P	S/R			YC053-YN236, YN501-YR328
3007B	20	Y7	WG		16-8	27-53-21	D40024J	14			D42104P	13			YC051-YC052
3007B	20	Y7	WG		16-6	27-53-21	D40024P	14			D42104P	13			YC053-YC057
3007B	20	Y7	WG		16-7	27-53-21	D40024P	14			D42104P	13			YC058-YD152
3007B	20	Y7	WG		16-5	27-53-21	D40024P	14			D42104P	13			YD153-YN236, YN501-YR328
3007R	20	Y7	WG		0-0	27-53-21	D40024J	13			D42104P	12			YC051-YC052
3007R	20	Y7	WG		0-0	27-53-21	D40024P	13			D42104P	12			YC053-YN236, YN501-YR328
3007Y	20	Y7	WG		0-0	27-53-21	D40024J	15			D42104P	14			YC051-YC052
3007Y	20	Y7	WG		0-0	27-53-21	D40024P	15			D42104P	14			YC053-YN236, YN501-YR328
3007Z			WG		0-0	27-53-21	D40024J	S/R			D42104P	S/R			YC051-YC052
3007Z			WG		0-0	27-53-21	D40024P	S/R			D42104P	S/R			YC053-YN236, YN501-YR328
3008B	20	Y7	WH		15-6	27-53-21	D11818	5			D42104P	17			YC051-YC052
3008B	20	Y7	WH		15-7	27-53-21	D11818	5			D42104P	17			YC053-YC057, YD153-YD158
3008B	20	Y7	WH		15-8	27-53-21	D11818	5			D42104P	17			YC058-YD152, YD160-YN236, YN501-YR328
3008R	20	Y7	WH		0-0	27-53-21	D11818	4			D42104P	16			YC051-YN236, YN501-YR328
3008Y	20	Y7	WH		0-0	27-53-21	D11818	3			D42104P	18			YC051-YN236, YN501-YR328
3008Z			WH		0-0	27-53-21	D11818	S/R			D42104P	S/R			YC051-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W1020

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1022	286A1022				L WING TRAILING EDGE:DISC BRACKET STA 254L TO W/W DISC & AFT CARGO DISC (continued)										
3009B	20	Y7	WI		7-0	27-53-21	D11820		5		D42104P	21			YC051-YC052
3009B	20	Y7	WI		7-1	27-53-21	D11820		5		D42104P	21			YC053-YC057
3009B	20	Y7	WI		6-9	27-53-21	D11820		5		D42104P	21			YC058-YD152
3009B	20	Y7	WI		6-10	27-53-21	D11820		5		D42104P	21			YD153-YN236, YN501-YR328
3009R	20	Y7	WI		0-0	27-53-21	D11820		4		D42104P	20			YC051-YN236, YN501-YR328
3009Y	20	Y7	WI		0-0	27-53-21	D11820		3		D42104P	22			YC051-YN236, YN501-YR328
3009Z			WI		0-0	27-53-21	D11820		S/R		D42104P	S/R			YC051-YN236, YN501-YR328
3011B	20	Y7	WK		16-1	27-62-14	D40024J		45		D42100P	17			YC051-YC052
3011B	20	Y7	WK		15-11	27-62-14	D40024P		45		D42100P	17			YC053-YD152
3011B	20	Y7	WK		15-9	27-62-14	D40024P		45		D42100P	17			YD153-YN236, YN501-YR328
3011R	20	Y7	WK		0-0	27-62-14	D40024J		44		D42100P	16			YC051-YC052
3011R	20	Y7	WK		0-0	27-62-14	D40024P		44		D42100P	16			YC053-YN236, YN501-YR328
3011Y	20	Y7	WK		0-0	27-62-14	D40024J		46		D42100P	18			YC051-YC052
3011Y	20	Y7	WK		0-0	27-62-14	D40024P		46		D42100P	18			YC053-YN236, YN501-YR328
3011Z			WK		0-0	27-62-14	D40024J		S/R		D42100P	S/R			YC051-YC052
3011Z			WK		0-0	27-62-14	D40024P		S/R		D42100P	S/R			YC053-YN236, YN501-YR328
W1024	286A1024				LEFT TRAILING EDGE:STA 525 TO L. WING DISC STA 254L										
0513	20	HL			1-2	27-52-11	D00275		15		GD00126	ST..	E		YC051-YN236, YN501-YR328
0516	20	HL			2-1	27-62-11	D13954		5		GD01064	ST..	E		YL953-YL999, YR301-YR328
0517	20	HL			1-9	27-62-11	D13954		3		GD01066	ST..	E		YL953-YL999, YR301-YR328
0518	20	HL			2-1	27-62-11	D13956		5		GD01080	ST..	E		YL953-YL999, YR301-YR328
0519	20	HL			1-10	27-62-11	D13956		3		GD01082	ST..	E		YL953-YL999, YR301-YR328
0520	20	HL			2-2	27-62-11	D13958		5		GD01072	ST..	E		YL953-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W1020

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1024	286A1024			LEFT TRAILING EDGE:STA 525 TO L. WING DISC STA 254L (continued)											
0521	20		HL		2-6	27-62-11	D13958		3		GD01074	ST..	E		YL953-YL999, YR301-YR328
0522	20		HL		2-1	27-62-11	D14126		5		GD01030	ST..	E		YL953-YL999, YR301-YR328
0523	20		HL		2-4	27-62-11	D14126		3		GD01022	ST..	E		YL953-YL999, YR301-YR328
1001	20		HP	AA	17-1	28-21-11	D00788		6		D40024P	34			YC051-YC052
1001	20		HP	AA	17-3	28-21-11	D00788		6		D40024J	34			YC053-YC055
1001	20		HP	AA	17-1	28-21-11	D00788		6		D40024J	34			YC056-YN236, YN501-YR328
1001Z				AA	0-0	28-21-11	D00788		S/R		D40024P	S/R			YC051-YC052
1001Z				AA	0-0	28-21-11	D00788		S/R		D40024J	S/R			YC053-YN236, YN501-YR328
1002	18		HP	AB	3-1	27-53-21	D11814		8		GD00126	ST..	E	*1	YC051-YC055
1002	18		HP	AB	2-8	27-53-21	D11814		8		GD00126	ST..	E	*1	YC056-YD158, YN231
1002	18		HP	AB	2-9	27-53-21	D11814		8		GD00126	ST..	E	*1	YD160-YL999, YN232-YN236, YN501-YR328
1002Z				AB	0-0	27-53-21	D11814		S/R		GD00126	ST..	E	*1	YC051-YN236, YN501-YR328
1003	18		HP	AC	8-8	27-53-21	D11816		8		GD00124	ST..	E	*2	YC051-YC052
1003	18		HP	AC	8-9	27-53-21	D11816		8		GD00124	ST..	E	*2	YC053-YC055
1003	18		HP	AC	8-7	27-53-21	D11816		8		GD00124	ST..	E	*2	YC056-YN236, YN501-YR328
1003Z				AC	0-0	27-53-21	D11816		S/R		GD00124	ST..	E	*2	YC051-YN236, YN501-YR328
2001B	20		Y6	GA	27-11	27-18-11	D03572		1		D40024P	7			YC051-YC052
2001B	20		Y6	GA	28-1	27-18-11	D03572		1		D40024J	7			YC053-YC055, YL955-YL968, YN236, YN501-YR301
2001B	20		Y6	GA	28-2	27-18-11	D03572		1		D40024J	7			YC056-YL954, YN231-YN235
2001B	20		Y6	GA	27-10	27-18-11	D03572		1		D40024J	7			YL969-YL999, YR303-YR328
2001R	20		Y6	GA	0-0	27-18-11	D03572		2		D40024P	6			YC051-YC052
2001R	20		Y6	GA	0-0	27-18-11	D03572		2		D40024J	6			YC053-YN236, YN501-YR328
2001Z				GA	0-0	27-18-11	GD00120	ST..	E		D40024P	S/R			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W1020

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1024	286A1024			LEFT TRAILING EDGE:STA 525 TO L. WING DISC STA 254L (continued)											
2001Z				GA	0-0	27-18-11	GD00120	ST..	E		D40024J	S/R			YC053-YN236, YN501-YR328
2002B	20	Y6	GB		12-11	22-11-31	D01699	1			D40024P	2			YC051-YC052
2002B	20	Y6	GB		13-3	22-11-31	D01699	1			D40024J	2			YC053-YC055
2002B	20	Y6	GB		13-0	22-11-31	D01699	1			D40024J	2			YC056-YC058, YL969-YL999, YR303-YR328
2002B	20	Y6	GB		13-2	22-11-31	D01699	1			D40024J	2			YC059-YL968, YN231-YN236, YN501-YR301
2002R	20	Y6	GB		0-0	22-11-31	D01699	2			D40024P	1			YC051-YC052
2002R	20	Y6	GB		0-0	22-11-31	D01699	2			D40024J	1			YC053-YN236, YN501-YR328
2002Z			GB		0-0	22-11-31	D01699	S/R			D40024P	S/R			YC051-YC052
2002Z			GB		0-0	22-11-31	D01699	S/R			D40024J	S/R			YC053-YN236, YN501-YR328
2003B	20	Y6	GC		13-1	22-11-31	D01695	1			D40024P	20			YC051-YC052
2003B	20	Y6	GC		13-3	22-11-31	D01695	1			D40024J	20			YC053-YC055
2003B	20	Y6	GC		13-2	22-11-31	D01695	1			D40024J	20			YC056-YC058
2003B	20	Y6	GC		13-1	22-11-31	D01695	1			D40024J	20			YC059-YL968, YN231-YN236, YN501-YR301
2003B	20	Y6	GC		12-10	22-11-31	D01695	1			D40024J	20			YL969-YL999, YR303-YR328
2003R	20	Y6	GC		0-0	22-11-31	D01695	2			D40024P	19			YC051-YC052
2003R	20	Y6	GC		0-0	22-11-31	D01695	2			D40024J	19			YC053-YN236, YN501-YR328
2003Z			GC		0-0	22-11-31	D01695	S/R			D40024P	S/R			YC051-YC052
2003Z			GC		0-0	22-11-31	D01695	S/R			D40024J	S/R			YC053-YN236, YN501-YR328
2004B	20	Y6	GD		20-11	27-32-21	D00275	5			D40024P	30			YC051-YC052
2004B	20	Y6	GD		21-1	27-32-21	D00275	5			D40024J	30			YC053-YC055, YD160-YL968, YN232-YN236, YN501-YR301
2004B	20	Y6	GD		21-0	27-32-21	D00275	5			D40024J	30			YC056-YD158, YN231
2004B	20	Y6	GD		20-10	27-32-21	D00275	5			D40024J	30			YL969-YL999, YR303-YR328
2004R	20	Y6	GD		0-0	27-32-21	D00275	4			D40024P	29			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W1020

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From			To			Effectivity		
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W1024	286A1024			LEFT TRAILING EDGE:STA 525 TO L. WING DISC STA 254L (continued)										
2004R	20	Y6	GD	0-0	27-32-21	D00275	4		D40024J	29		YC053-YN236, YN501-YR328		
2004Z			GD	0-0	27-32-21	D00275	S/R		D40024P	S/R		YC051-YC052		
2004Z			GD	0-0	27-32-21	D00275	S/R		D40024J	S/R		YC053-YN236, YN501-YR328		
2005B	20	Y6	GE	20-11	22-11-11	D00275	10		D40024P	25		YC051-YC052		
2005B	20	Y6	GE	21-1	22-11-11	D00275	10		D40024J	25		YC053-YC055, YD160-YL968, YN232-YN236, YN501-YR301		
2005B	20	Y6	GE	21-0	22-11-11	D00275	10		D40024J	25		YC056-YD158, YN231		
2005B	20	Y6	GE	20-10	22-11-11	D00275	10		D40024J	25		YL969-YL999, YR303-YR328		
2005R	20	Y6	GE	0-0	22-11-11	D00275	9		D40024P	24		YC051-YC052		
2005R	20	Y6	GE	0-0	22-11-11	D00275	9		D40024J	24		YC053-YN236, YN501-YR328		
2005Z			GE	0-0	22-11-11	D00275	S/R		D40024P	S/R		YC051-YC052		
2005Z			GE	0-0	22-11-11	D00275	S/R		D40024J	S/R		YC053-YN236, YN501-YR328		
2006B	20	M2	GF	20-11	27-52-11	D00275	2		D40024P	37		YC051-YC052		
2006B	20	M2	GF	21-1	27-52-11	D00275	2		D40024J	37		YC053-YC055, YD160-YL968, YN232-YN236, YN501-YR301		
2006B	20	M2	GF	21-0	27-52-11	D00275	2		D40024J	37		YC056-YD158, YN231		
2006B	20	M2	GF	20-10	27-52-11	D00275	2		D40024J	37		YL969-YL999, YR303-YR328		
2006R	20	M2	GF	0-0	27-52-11	D00275	1		D40024P	36		YC051-YC052		
2006R	20	M2	GF	0-0	27-52-11	D00275	1		D40024J	36		YC053-YN236, YN501-YR328		
2006ZI			GF	0-0	27-52-11	D00275	S/R		D40024P	38	18	YC051-YC052		
2006ZI			GF	0-0	27-52-11	D00275	S/R		D40024J	38		YC053-YN236, YN501-YR328		
2006ZO			GF	0-0	27-52-11	D00275	S/R		D40024P	S/R		YC051-YC052		
2006ZO			GF	0-0	27-52-11	D00275	S/R		D40024J	S/R		YC053-YN236, YN501-YR328		
2007B	20	M2	GG	20-11	27-52-11	D00275	3		D40024P	41		YC051-YC052		

WIRE LIST

D280A108

91-21-11

Section W1020

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Description Fam FT-IN		Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W1024	286A1024			LEFT TRAILING EDGE:STA 525 TO L. WING DISC STA 254L (continued)											
2007B	20	M2	GG		21-1	27-52-11	D00275		3		D40024J	41			YC053-YC055, YD160-YL968, YN232-YN236, YN501-YR301
2007B	20	M2	GG		21-0	27-52-11	D00275		3		D40024J	41			YC056-YD158, YN231
2007B	20	M2	GG		20-10	27-52-11	D00275		3		D40024J	41			YL969-YL999, YR303-YR328
2007R	20	M2	GG		0-0	27-52-11	D00275		11		D40024P	40			YC051-YC052
2007R	20	M2	GG		0-0	27-52-11	D00275		11		D40024J	40			YC053-YN236, YN501-YR328
2007ZI			GG		0-0	27-52-11	D00275		S/R		D40024P	39	18		YC051-YC052
2007ZI			GG		0-0	27-52-11	D00275		S/R		D40024J	39			YC053-YN236, YN501-YR328
2007ZO			GG		0-0	27-52-11	D00275		S/R		D40024P	S/R			YC051-YC052
2007ZO			GG		0-0	27-52-11	D00275		S/R		D40024J	S/R			YC053-YN236, YN501-YR328
2008B	20	Y6	GI		18-3	27-53-21	D11816		7		D11814	1			YC051-YC055
2008B	20	Y6	GI		18-0	27-53-21	D11816		7		D11814	1			YC056-YD158, YN231
2008B	20	Y6	GI		18-2	27-53-21	D11816		7		D11814	1			YD160-YL999, YN232-YN236, YN501-YR328
2008R	20	Y6	GI		0-0	27-53-21	D11816		6		D11814	2			YC051-YN236, YN501-YR328
2008Z			GI		0-0	27-53-21	D11816		S/R		D11814	S/R			YC051-YN236, YN501-YR328
2009B	20	Y6	GH		11-10	27-53-21	D11816		1		D40024P	12			YC051-YC052
2009B	20	Y6	GH		12-1	27-53-21	D11816		1		D40024J	12			YC053-YC055
2009B	20	Y6	GH		11-10	27-53-21	D11816		1		D40024J	12			YC056-YL968, YN231-YN236, YN501-YR301
2009B	20	Y6	GH		11-8	27-53-21	D11816		1		D40024J	12			YL969-YL999, YR303-YR328
2009R	20	Y6	GH		0-0	27-53-21	D11816		2		D40024P	11			YC051-YC052
2009R	20	Y6	GH		0-0	27-53-21	D11816		2		D40024J	11			YC053-YN236, YN501-YR328
2009Z			GH		0-0	27-53-21	D11816		S/R		D40024P	S/R			YC051-YC052
2009Z			GH		0-0	27-53-21	D11816		S/R		D40024J	S/R			YC053-YN236, YN501-YR328
2011B	20	Y6	GK		12-0	27-62-14	D10539		1		D40024P	43			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W1020

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W1024	286A1024			LEFT TRAILING EDGE:STA 525 TO L. WING DISC STA 254L (continued)										
2011B	20	Y6	GK	12-2	27-62-14	D10539		1		D40024J	43		YC053-YC055, YD160-YL968, YN232-YN236, YN501-YR301	
2011B	20	Y6	GK	12-1	27-62-14	D10539		1		D40024J	43		YC056-YD158, YN231	
2011B	20	Y6	GK	11-11	27-62-14	D10539		1		D40024J	43		YL969-YL999, YR303-YR328	
2011R	20	Y6	GK	0-0	27-62-14	D10539		2		D40024P	42		YC051-YC052	
2011R	20	Y6	GK	0-0	27-62-14	D10539		2		D40024J	42		YC053-YN236, YN501-YR328	
2011Z			GK	0-0	27-62-14	GD00122	ST..	E		D40024P	S/R		YC051-YC052	
2011Z			GK	0-0	27-62-14	GD00122	ST..	E		D40024J	S/R		YC053-YN236, YN501-YR328	
2012B	20	Y6	OL	15-9	27-62-11	D13954		4		D40024J	48		YL953-YL968, YR301	
2012B	20	Y6	OL	15-6	27-62-11	D13954		4		D40024J	48		YL969-YL999, YR303-YR328	
2012R	20	Y6	OL	0-0	27-62-11	D13954		1		D40024J	47		YL953-YL999, YR301-YR328	
2012Z			OL	0-0	27-62-11	D13954		S/R		D40024J	S/R		YL953-YL999, YR301-YR328	
2013B	20	Y6	OM	13-4	27-62-11	D13956		4		D40024J	50		YL953-YL968, YR301	
2013B	20	Y6	OM	13-1	27-62-11	D13956		4		D40024J	50		YL969-YL999, YR303-YR328	
2013R	20	Y6	OM	0-0	27-62-11	D13956		1		D40024J	49		YL953-YL999, YR301-YR328	
2013Z			OM	0-0	27-62-11	D13956		S/R		D40024J	S/R		YL953-YL999, YR301-YR328	
2014B	20	Y6	ON	10-6	27-62-11	D13958		4		D40024J	52		YL953-YL968, YR301	
2014B	20	Y6	ON	10-3	27-62-11	D13958		4		D40024J	52		YL969-YL999, YR303-YR328	
2014R	20	Y6	ON	0-0	27-62-11	D13958		1		D40024J	51		YL953-YL999, YR301-YR328	
2014Z			ON	0-0	27-62-11	D13958		S/R		D40024J	S/R		YL953-YL999, YR301-YR328	
2015B	20	Y6	OP	6-8	27-62-11	D14126		4		D40024J	54		YL953-YL968, YR301	
2015B	20	Y6	OP	6-5	27-62-11	D14126		4		D40024J	54		YL969-YL999, YR303-YR328	
2015R	20	Y6	OP	0-0	27-62-11	D14126		1		D40024J	53		YL953-YL999, YR301-YR328	

WIRE LIST

D280A108

91-21-11

Section W1020

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Description Fam	Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W1024	286A1024			LEFT TRAILING EDGE: STA 525 TO L. WING DISC STA 254L (continued)										
2015Z				OP	0-0	27-62-11	D14126	S/R		D40024J	S/R			YL953-YL999, YR301-YR328
3001B	20	Y7	WA		27-11	27-18-11	D03572	5		D40024P	9			YC051-YC052
3001B	20	Y7	WA		28-1	27-18-11	D03572	5		D40024J	9			YC053-YC055, YL955-YL968, YN236, YN501-YR301
3001B	20	Y7	WA		28-2	27-18-11	D03572	5		D40024J	9			YC056-YL954, YN231-YN235
3001B	20	Y7	WA		27-10	27-18-11	D03572	5		D40024J	9			YL969-YL999, YR303-YR328
3001R	20	Y7	WA		0-0	27-18-11	D03572	4		D40024P	8			YC051-YC052
3001R	20	Y7	WA		0-0	27-18-11	D03572	4		D40024J	8			YC053-YN236, YN501-YR328
3001Y	20	Y7	WA		0-0	27-18-11	D03572	3		D40024P	10			YC051-YC052
3001Y	20	Y7	WA		0-0	27-18-11	D03572	3		D40024J	10			YC053-YN236, YN501-YR328
3001Z			WA		0-0	27-18-11	GD00120	ST..	E	D40024P	S/R			YC051-YC052
3001Z			WA		0-0	27-18-11	GD00120	ST..	E	D40024J	S/R			YC053-YN236, YN501-YR328
3002B	20	Y7	WB		12-11	22-11-31	D01699	5		D40024P	4			YC051-YC052
3002B	20	Y7	WB		13-3	22-11-31	D01699	5		D40024J	4			YC053-YC055
3002B	20	Y7	WB		13-0	22-11-31	D01699	5		D40024J	4			YC056-YC058, YL969-YL999, YR303-YR314
3002B	20	Y7	WB		13-2	22-11-31	D01699	5		D40024J	4			YC059-YL968, YN231-YN236, YN501-YR301
3002B	20	Y6	WB		13-0	22-11-31	D01699	5		D40024J	4			YR315-YR328
3002R	20	Y7	WB		0-0	22-11-31	D01699	4		D40024P	3			YC051-YC052
3002R	20	Y7	WB		0-0	22-11-31	D01699	4		D40024J	3			YC053-YN236, YN501-YR314
3002R	20	Y6	WB		0-0	22-11-31	D01699	4		D40024J	3			YR315-YR328
3002Y	20	Y7	WB		0-0	22-11-31	D01699	3		D40024P	5			YC051-YC052
3002Y	20	Y7	WB		0-0	22-11-31	D01699	3		D40024J	5			YC053-YN236, YN501-YR314
3002Z			WB		0-0	22-11-31	D01699	S/R		D40024P	S/R			YC051-YC052
3002Z			WB		0-0	22-11-31	D01699	S/R		D40024J	S/R			YC053-YN236, YN501-YR328
3003B	20	Y7	WC		13-1	22-11-31	D01695	5		D40024P	22			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W1020

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description		From				To					
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W1024		286A1024			LEFT TRAILING EDGE:STA 525 TO L. WING DISC STA 254L (continued)											
3003B	20		Y7	WC	13-3	22-11-31	D01695		5		D40024J	22			YC053-YC055	
3003B	20		Y7	WC	13-2	22-11-31	D01695		5		D40024J	22			YC056-YC058	
3003B	20		Y7	WC	13-1	22-11-31	D01695		5		D40024J	22			YC059-YL968, YN231-YN236, YN501-YR301	
3003B	20		Y7	WC	12-10	22-11-31	D01695		5		D40024J	22			YL969-YL999, YR303-YR314	
3003B	20		Y6	WC	12-10	22-11-31	D01695		5		D40024J	22			YR315-YR328	
3003R	20		Y7	WC	0-0	22-11-31	D01695		4		D40024P	21			YC051-YC052	
3003R	20		Y7	WC	0-0	22-11-31	D01695		4		D40024J	21			YC053-YN236, YN501-YR314	
3003R	20		Y6	WC	0-0	22-11-31	D01695		4		D40024J	21			YR315-YR328	
3003Y	20		Y7	WC	0-0	22-11-31	D01695		3		D40024P	23			YC051-YC052	
3003Y	20		Y7	WC	0-0	22-11-31	D01695		3		D40024J	23			YC053-YN236, YN501-YR314	
3003Z				WC	0-0	22-11-31	D01695		S/R		D40024P	S/R			YC051-YC052	
3003Z				WC	0-0	22-11-31	D01695		S/R		D40024J	S/R			YC053-YN236, YN501-YR328	
3004B	20		Y7	WD	20-11	27-32-21	D00275		7		D40024P	32			YC051-YC052	
3004B	20		Y7	WD	21-1	27-32-21	D00275		7		D40024J	32			YC053-YC055, YD160-YL968, YN232-YN236, YN501-YR301	
3004B	20		Y7	WD	21-0	27-32-21	D00275		7		D40024J	32			YC056-YD158, YN231	
3004B	20		Y7	WD	20-10	27-32-21	D00275		7		D40024J	32			YL969-YL999, YR303-YR328	
3004R	20		Y7	WD	0-0	27-32-21	D00275		6		D40024P	31			YC051-YC052	
3004R	20		Y7	WD	0-0	27-32-21	D00275		6		D40024J	31			YC053-YN236, YN501-YR328	
3004Y	20		Y7	WD	0-0	27-32-21	D00275		8		D40024P	33			YC051-YC052	
3004Y	20		Y7	WD	0-0	27-32-21	D00275		8		D40024J	33			YC053-YN236, YN501-YR328	
3004Z				WD	0-0	27-32-21	D00275		S/R		D40024P	S/R			YC051-YC052	
3004Z				WD	0-0	27-32-21	D00275		S/R		D40024J	S/R			YC053-YN236, YN501-YR328	
3005B	20		Y7	WE	20-11	22-12-31	D00275		13		D40024P	27			YC051-YC052	

WIRE LIST

D280A108

91-21-11

Section W1020

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1024	286A1024				LEFT TRAILING EDGE: STA 525 TO L. WING DISC STA 254L (continued)										
3005B	20	Y7	WE		21-1	22-12-31	D00275	13			D40024J	27			YC053-YC055, YD160-YL968, YN232-YN236, YN501-YR301
3005B	20	Y7	WE		21-0	22-12-31	D00275	13			D40024J	27			YC056-YD158, YN231
3005B	20	Y7	WE		20-10	22-12-31	D00275	13			D40024J	27			YL969-YL999, YR303-YR328
3005R	20	Y7	WE		0-0	22-12-31	D00275	12			D40024P	26			YC051-YC052
3005R	20	Y7	WE		0-0	22-12-31	D00275	12			D40024J	26			YC053-YN236, YN501-YR328
3005Y	20	Y7	WE		0-0	22-12-31	D00275	14			D40024P	28			YC051-YC052
3005Y	20	Y7	WE		0-0	22-12-31	D00275	14			D40024J	28			YC053-YN236, YN501-YR328
3005Z			WE		0-0	22-12-31	D00275	S/R			D40024P	S/R			YC051-YC052
3005Z			WE		0-0	22-12-31	D00275	S/R			D40024J	S/R			YC053-YN236, YN501-YR328
3006B	20	Y7	WF		22-7	27-53-21	D11814	5			D40024P	17			YC051-YC052
3006B	20	Y7	WF		22-9	27-53-21	D11814	5			D40024J	17			YC053-YC055, YD160-YL968, YN232-YN236, YN501-YR301
3006B	20	Y7	WF		22-8	27-53-21	D11814	5			D40024J	17			YC056-YD158, YN231
3006B	20	Y7	WF		22-7	27-53-21	D11814	5			D40024J	17			YL969-YL999, YR303-YR328
3006R	20	Y7	WF		0-0	27-53-21	D11814	4			D40024P	16			YC051-YC052
3006R	20	Y7	WF		0-0	27-53-21	D11814	4			D40024J	16			YC053-YN236, YN501-YR328
3006Y	20	Y7	WF		0-0	27-53-21	D11814	3			D40024P	18			YC051-YC052
3006Y	20	Y7	WF		0-0	27-53-21	D11814	3			D40024J	18			YC053-YN236, YN501-YR328
3006Z			WF		0-0	27-53-21	D11814	S/R			D40024P	S/R			YC051-YC052
3006Z			WF		0-0	27-53-21	D11814	S/R			D40024J	S/R			YC053-YN236, YN501-YR328
3007B	20	Y7	WG		11-10	27-53-21	D11816	5			D40024P	14			YC051-YC052
3007B	20	Y7	WG		12-1	27-53-21	D11816	5			D40024J	14			YC053-YC055
3007B	20	Y7	WG		11-10	27-53-21	D11816	5			D40024J	14			YC056-YL968, YN231-YN236, YN501-YR301

WIRE LIST

D280A108

91-21-11

Section W1020

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1024	286A1024				LEFT TRAILING EDGE: STA 525 TO L. WING DISC STA 254L (continued)										
3007B	20	Y7	WG		11-8	27-53-21	D11816		5		D40024J		14		YL969-YL999, YR303-YR328
3007R	20	Y7	WG		0-0	27-53-21	D11816		4		D40024P		13		YC051-YC052
3007R	20	Y7	WG		0-0	27-53-21	D11816		4		D40024J		13		YC053-YN236, YN501-YR328
3007Y	20	Y7	WG		0-0	27-53-21	D11816		3		D40024P		15		YC051-YC052
3007Y	20	Y7	WG		0-0	27-53-21	D11816		3		D40024J		15		YC053-YN236, YN501-YR328
3007Z			WG		0-0	27-53-21	D11816		S/R		D40024P		S/R		YC051-YC052
3007Z			WG		0-0	27-53-21	D11816		S/R		D40024J		S/R		YC053-YN236, YN501-YR328
3011B	20	Y7	WK		12-0	27-62-14	D10539		5		D40024P		45		YC051-YC052
3011B	20	Y7	WK		12-2	27-62-14	D10539		5		D40024J		45		YC053-YC055, YD160-YL968, YN232-YN236, YN501-YR301
3011B	20	Y7	WK		12-1	27-62-14	D10539		5		D40024J		45		YC056-YD158, YN231
3011B	20	Y7	WK		11-11	27-62-14	D10539		5		D40024J		45		YL969-YL999, YR303-YR328
3011R	20	Y7	WK		0-0	27-62-14	D10539		4		D40024P		44		YC051-YC052
3011R	20	Y7	WK		0-0	27-62-14	D10539		4		D40024J		44		YC053-YN236, YN501-YR328
3011Y	20	Y7	WK		0-0	27-62-14	D10539		3		D40024P		46		YC051-YC052
3011Y	20	Y7	WK		0-0	27-62-14	D10539		3		D40024J		46		YC053-YN236, YN501-YR328
3011Z			WK		0-0	27-62-14	GD00122	ST..	E		D40024P		S/R		YC051-YC052
3011Z			WK		0-0	27-62-14	GD00122	ST..	E		D40024J		S/R		YC053-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W1020

Page 17 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1032	286A1032				R WING TRAILNG EDGE:DISC BRACKET STA 254R TO W/W DISC & AFT CARGO DISC										
1001	20	HP	AA		14-9	28-21-11	D40034J	34			D43104P	25			YC051-YC052
1001	20	HP	AA		14-7	28-21-11	D40034P	34			D43104P	25			YC053-YD152
1001	20	HP	AA		14-5	28-21-11	D40034P	34			D43104P	25			YD153-YN236, YN501-YR328
1001Z			AA		0-0	28-21-11	D40034J	S/R			D43104P	S/R			YC051-YC052
1001Z			AA		0-0	28-21-11	D40034P	S/R			D43104P	S/R			YC053-YN236, YN501-YR328
1002	18	HP	AB		3-11	27-53-21	D11824	8			GD00234	ST..	E	*1	YC051-YC052
1002	18	HP	AB		4-0	27-53-21	D11824	8			GD00234	ST..	E	*1	YC053-YN236, YN501-YR328
1002Z			AB		0-0	27-53-21	D11824	S/R			GD00234	ST..	E	*1	YC051-YN236, YN501-YR328
1003	18	HP	AC		4-8	27-53-21	D11822	8			GD00236	ST..	E	*2	YC051-YC052
1003	18	HP	AC		4-9	27-53-21	D11822	8			GD00236	ST..	E	*2	YC053-YD152
1003	18	HP	AC		4-2	27-53-21	D11822	8			GD00236	ST..	E	*2	YD153-YN236, YN501-YR328
1003Z			AC		0-0	27-53-21	D11822	S/R			GD00236	ST..	E	*2	YC051-YN236, YN501-YR328
2001B	20	Y6	GA		15-7	27-18-11	D40034J	7			D43100P	2			YC051-YC052
2001B	20	Y6	GA		15-5	27-18-11	D40034P	7			D43100P	2			YC053-YD152
2001B	20	Y6	GA		16-5	27-18-11	D40034P	7			D43100P	2			YD153-YN236, YN501-YR328
2001R	20	Y6	GA		0-0	27-18-11	D40034J	6			D43100P	1			YC051-YC052
2001R	20	Y6	GA		0-0	27-18-11	D40034P	6			D43100P	1			YC053-YN236, YN501-YR328
2001Z			GA		0-0	27-18-11	D40034J	S/R			D43100P	S/R			YC051-YC052
2001Z			GA		0-0	27-18-11	D40034P	S/R			D43100P	S/R			YC053-YN236, YN501-YR328
2002B	20	Y6	GB		15-7	22-11-31	D40034J	2			D43100P	4			YC051-YC052
2002B	20	Y6	GB		15-5	22-11-31	D40034P	2			D43100P	4			YC053-YD152
2002B	20	Y6	GB		16-5	22-11-31	D40034P	2			D43100P	4			YD153-YN236, YN501-YR328
2002R	20	Y6	GB		0-0	22-11-31	D40034J	1			D43100P	3			YC051-YC052
2002R	20	Y6	GB		0-0	22-11-31	D40034P	1			D43100P	3			YC053-YN236, YN501-YR328
2002Z			GB		0-0	22-11-31	D40034J	S/R			D43100P	S/R			YC051-YC052
2002Z			GB		0-0	22-11-31	D40034P	S/R			D43100P	S/R			YC053-YN236, YN501-YR328
2003B	20	Y6	GC		17-3	22-11-31	D40034J	20			D43102P	2			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W1030

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W1032	286A1032				R WING TRAILNG EDGE:DISC BRACKET STA 254R TO W/W DISC & AFT CARGO DISC (continued)											
2003B	20	Y6	GC		17-0	22-11-31	D40034P	20			D43102P	2			YC053-YD152	
2003B	20	Y6	GC		17-3	22-11-31	D40034P	20			D43102P	2			YD153-YN236, YN501-YR328	
2003R	20	Y6	GC		0-0	22-11-31	D40034J	19			D43102P	1			YC051-YC052	
2003R	20	Y6	GC		0-0	22-11-31	D40034P	19			D43102P	1			YC053-YN236, YN501-YR328	
2003Z			GC		0-0	22-11-31	D40034J	S/R			D43102P	S/R			YC051-YC052	
2003Z			GC		0-0	22-11-31	D40034P	S/R			D43102P	S/R			YC053-YN236, YN501-YR328	
2004B	20	Y6	GD		15-7	27-32-11	D40034J	30			D43100P	21			YC051-YC052	
2004B	20	Y6	GD		15-5	27-32-11	D40034P	30			D43100P	21			YC053-YD152	
2004B	20	Y6	GD		16-5	27-32-11	D40034P	30			D43100P	21			YD153-YN236, YN501-YR328	
2004R	20	Y6	GD		0-0	27-32-11	D40034J	29			D43100P	20			YC051-YC052	
2004R	20	Y6	GD		0-0	27-32-11	D40034P	29			D43100P	20			YC053-YN236, YN501-YR328	
2004Z			GD		0-0	27-32-11	D40034J	S/R			D43100P	S/R			YC051-YC052	
2004Z			GD		0-0	27-32-11	D40034P	S/R			D43100P	S/R			YC053-YN236, YN501-YR328	
2005B	20	Y6	GE		17-3	22-11-11	D40034J	25			D43102P	4			YC051-YC052	
2005B	20	Y6	GE		17-0	22-11-11	D40034P	25			D43102P	4			YC053-YD152	
2005B	20	Y6	GE		17-3	22-11-11	D40034P	25			D43102P	4			YD153-YN236, YN501-YR328	
2005R	20	Y6	GE		0-0	22-11-11	D40034J	24			D43102P	3			YC051-YC052	
2005R	20	Y6	GE		0-0	22-11-11	D40034P	24			D43102P	3			YC053-YN236, YN501-YR328	
2005Z			GE		0-0	22-11-11	D40034J	S/R			D43102P	S/R			YC051-YC052	
2005Z			GE		0-0	22-11-11	D40034P	S/R			D43102P	S/R			YC053-YN236, YN501-YR328	
2006B	20	M2	GF		14-9	27-52-11	D40034J	37			D43104P	2			YC051-YC052	
2006B	20	M2	GF		14-7	27-52-11	D40034P	37			D43104P	2			YC053-YD152	
2006B	20	M2	GF		14-5	27-52-11	D40034P	37			D43104P	2			YD153-YN236, YN501-YR328	
2006R	20	M2	GF		0-0	27-52-11	D40034J	36			D43104P	1			YC051-YC052	
2006R	20	M2	GF		0-0	27-52-11	D40034P	36			D43104P	1			YC053-YN236, YN501-YR328	
2006ZI			GF		0-0	27-52-11	D40034J	38			D43104P	3			YC051-YC052	
2006ZI			GF		0-0	27-52-11	D40034P	38			D43104P	3			YC053-YN236, YN501-YR328	

WIRE LIST

D280A108

91-21-11

Section W1030

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1032	286A1032			R WING TRAILNG EDGE:DISC BRACKET STA 254R TO W/W DISC & AFT CARGO DISC (continued)											
2006ZO				GF	0-0	27-52-11	D40034J		S/R		D43104P		S/R		YC051-YC052
2006ZO				GF	0-0	27-52-11	D40034P		S/R		D43104P		S/R		YC053-YN236, YN501-YR328
2007B	20	M2		GG	14-9	27-52-11	D40034J		41		D43104P		5		YC051-YC052
2007B	20	M2		GG	14-7	27-52-11	D40034P		41		D43104P		5		YC053-YD152
2007B	20	M2		GG	14-5	27-52-11	D40034P		41		D43104P		5		YD153-YN236, YN501-YR328
2007R	20	M2		GG	0-0	27-52-11	D40034J		40		D43104P		4		YC051-YC052
2007R	20	M2		GG	0-0	27-52-11	D40034P		40		D43104P		4		YC053-YN236, YN501-YR328
2007ZI				GG	0-0	27-52-11	D40034J		39		D43104P		6		YC051-YC052
2007ZI				GG	0-0	27-52-11	D40034P		39		D43104P		6		YC053-YN236, YN501-YR328
2007ZO				GG	0-0	27-52-11	D40034J		S/R		D43104P		S/R		YC051-YC052
2007ZO				GG	0-0	27-52-11	D40034P		S/R		D43104P		S/R		YC053-YN236, YN501-YR328
2008B	20	Y6		GI	12-1	27-53-21	D11824		1		D11822		7		YC051-YC052
2008B	20	Y6		GI	12-3	27-53-21	D11824		1		D11822		7		YC053-YD152
2008B	20	Y6		GI	12-6	27-53-21	D11824		1		D11822		7		YD153-YN236, YN501-YR328
2008R	20	Y6		GI	0-0	27-53-21	D11824		2		D11822		6		YC051-YN236, YN501-YR328
2008Z				GI	0-0	27-53-21	D11824		S/R		D11822		S/R		YC051-YN236, YN501-YR328
2009B	20	Y6		GH	4-4	27-53-21	D11824		7		D40034J		12		YC051-YC052
2009B	20	Y6		GH	4-3	27-53-21	D11824		7		D40034P		12		YC053-YN236, YN501-YR328
2009R	20	Y6		GH	0-0	27-53-21	D11824		6		D40034J		11		YC051-YC052
2009R	20	Y6		GH	0-0	27-53-21	D11824		6		D40034P		11		YC053-YN236, YN501-YR328
2009Z				GH	0-0	27-53-21	D11824		S/R		D40034J		S/R		YC051-YC052
2009Z				GH	0-0	27-53-21	D11824		S/R		D40034P		S/R		YC053-YN236, YN501-YR328
2010B	20	Y6		GJ	4-3	27-53-21	D11822		1		D43104P		8		YC051-YC052
2010B	20	Y6		GJ	4-4	27-53-21	D11822		1		D43104P		8		YC053-YD152
2010B	20	Y6		GJ	4-1	27-53-21	D11822		1		D43104P		8		YD153-YN236, YN501-YR328
2010R	20	Y6		GJ	0-0	27-53-21	D11822		2		D43104P		7		YC051-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W1030

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W1032	286A1032			R WING TRAILNG EDGE:DISC BRACKET STA 254R TO W/W DISC & AFT CARGO DISC (continued)												
2010Z				GJ	0-0	27-53-21		D11822		S/R		D43104P		S/R		YC051-YN236, YN501-YR328
2011B	20	Y6		GK	15-7	27-62-14		D40034J		43		D43100P		12		YC051-YC052
2011B	20	Y6		GK	15-5	27-62-14		D40034P		43		D43100P		12		YC053-YD152
2011B	20	Y6		GK	16-5	27-62-14		D40034P		43		D43100P		12		YD153-YN236, YN501-YR328
2011R	20	Y6		GK	0-0	27-62-14		D40034J		42		D43100P		11		YC051-YC052
2011R	20	Y6		GK	0-0	27-62-14		D40034P		42		D43100P		11		YC053-YN236, YN501-YR328
2011Z				GK	0-0	27-62-14		D40034J		S/R		D43100P		S/R		YC051-YC052
2011Z				GK	0-0	27-62-14		D40034P		S/R		D43100P		S/R		YC053-YN236, YN501-YR328
2012B	20	Y6		OL	16-5	27-62-11		D40034P		48		D43100P		30		YL953-YL999, YR301-YR328
2012R	20	Y6		OL	0-0	27-62-11		D40034P		47		D43100P		29		YL953-YL999, YR301-YR328
2012Z				OL	0-0	27-62-11		D40034P		S/R		D43100P		S/R		YL953-YL999, YR301-YR328
2013B	20	Y6		OM	16-5	27-62-11		D40034P		50		D43100P		32		YL953-YL999, YR301-YR328
2013R	20	Y6		OM	0-0	27-62-11		D40034P		49		D43100P		31		YL953-YL999, YR301-YR328
2013Z				OM	0-0	27-62-11		D40034P		S/R		D43100P		S/R		YL953-YL999, YR301-YR328
2014B	20	Y6		ON	16-5	27-62-11		D40034P		52		D43100P		34		YL953-YL999, YR301-YR328
2014R	20	Y6		ON	0-0	27-62-11		D40034P		51		D43100P		33		YL953-YL999, YR301-YR328
2014Z				ON	0-0	27-62-11		D40034P		S/R		D43100P		S/R		YL953-YL999, YR301-YR328
2015B	20	Y6		OP	16-5	27-62-11		D40034P		54		D43100P		36		YL953-YL999, YR301-YR328
2015R	20	Y6		OP	0-0	27-62-11		D40034P		53		D43100P		35		YL953-YL999, YR301-YR328
2015Z				OP	0-0	27-62-11		D40034P		S/R		D43100P		S/R		YL953-YL999, YR301-YR328
3001B	20	Y7		WA	15-7	27-18-11		D40034J		9		D43100P		6		YC051-YC052
3001B	20	Y7		WA	15-5	27-18-11		D40034P		9		D43100P		6		YC053-YD152

WIRE LIST

D280A108

91-21-11

Section W1030

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1032	286A1032			R WING TRAILNG EDGE:DISC BRACKET STA 254R TO W/W DISC & AFT CARGO DISC (continued)											
3001B	20	Y7	WA		16-5	27-18-11	D40034P		9		D43100P		6		YD153-YN236, YN501-YR328
3001R	20	Y7	WA		0-0	27-18-11	D40034J		8		D43100P		5		YC051-YC052
3001R	20	Y7	WA		0-0	27-18-11	D40034P		8		D43100P		5		YC053-YN236, YN501-YR328
3001Y	20	Y7	WA		0-0	27-18-11	D40034J		10		D43100P		7		YC051-YC052
3001Y	20	Y7	WA		0-0	27-18-11	D40034P		10		D43100P		7		YC053-YN236, YN501-YR328
3001Z			WA		0-0	27-18-11	D40034J		S/R		D43100P		S/R		YC051-YC052
3001Z			WA		0-0	27-18-11	D40034P		S/R		D43100P		S/R		YC053-YN236, YN501-YR328
3002B	20	Y7	WB		15-7	22-11-31	D40034J		4		D43100P		9		YC051-YC052
3002B	20	Y7	WB		15-5	22-11-31	D40034P		4		D43100P		9		YC053-YD152
3002B	20	Y7	WB		16-5	22-11-31	D40034P		4		D43100P		9		YD153-YN236, YN501-YR314
3002B	20	Y6	WB		16-5	22-11-31	D40034P		4		D43100P		9		YR315-YR328
3002R	20	Y7	WB		0-0	22-11-31	D40034J		3		D43100P		8		YC051-YC052
3002R	20	Y7	WB		0-0	22-11-31	D40034P		3		D43100P		8		YC053-YN236, YN501-YR314
3002R	20	Y6	WB		0-0	22-11-31	D40034P		3		D43100P		8		YR315-YR328
3002Y	20	Y7	WB		0-0	22-11-31	D40034J		5		D43100P		10		YC051-YC052
3002Y	20	Y7	WB		0-0	22-11-31	D40034P		5		D43100P		10		YC053-YN236, YN501-YR314
3002Z			WB		0-0	22-11-31	D40034J		S/R		D43100P		S/R		YC051-YC052
3002Z			WB		0-0	22-11-31	D40034P		S/R		D43100P		S/R		YC053-YN236, YN501-YR328
3003B	20	Y7	WC		17-3	22-11-31	D40034J		22		D43102P		6		YC051-YC052
3003B	20	Y7	WC		17-0	22-11-31	D40034P		22		D43102P		6		YC053-YD152
3003B	20	Y7	WC		17-3	22-11-31	D40034P		22		D43102P		6		YD153-YN236, YN501-YR314
3003B	20	Y6	WC		17-3	22-11-31	D40034P		22		D43102P		6		YR315-YR328
3003R	20	Y7	WC		0-0	22-11-31	D40034J		21		D43102P		5		YC051-YC052
3003R	20	Y7	WC		0-0	22-11-31	D40034P		21		D43102P		5		YC053-YN236, YN501-YR314
3003R	20	Y6	WC		0-0	22-11-31	D40034P		21		D43102P		5		YR315-YR328
3003Y	20	Y7	WC		0-0	22-11-31	D40034J		23		D43102P		7		YC051-YC052
3003Y	20	Y7	WC		0-0	22-11-31	D40034P		23		D43102P		7		YC053-YN236, YN501-YR314
3003Z			WC		0-0	22-11-31	D40034J		S/R		D43102P		S/R		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W1030

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description			From	To			Effectivity				
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1032	286A1032	R WING TRAILNG EDGE:DISC BRACKET STA 254R TO W/W DISC & AFT CARGO DISC (continued)											
3003Z			WC	0-0	22-11-31	D40034P	S/R		D43102P	S/R			YC053-YN236, YN501-YR328
3004B	20	Y7	WD	15-7	27-32-11	D40034J	32		D43100P	25			YC051-YC052
3004B	20	Y7	WD	15-5	27-32-11	D40034P	32		D43100P	25			YC053-YD152
3004B	20	Y7	WD	16-5	27-32-11	D40034P	32		D43100P	25			YD153-YN236, YN501-YR328
3004R	20	Y7	WD	0-0	27-32-11	D40034J	31		D43100P	24			YC051-YC052
3004R	20	Y7	WD	0-0	27-32-11	D40034P	31		D43100P	24			YC053-YN236, YN501-YR328
3004Y	20	Y7	WD	0-0	27-32-11	D40034J	33		D43100P	26			YC051-YC052
3004Y	20	Y7	WD	0-0	27-32-11	D40034P	33		D43100P	26			YC053-YN236, YN501-YR328
3004Z			WD	0-0	27-32-11	D40034J	S/R		D43100P	S/R			YC051-YC052
3004Z			WD	0-0	27-32-11	D40034P	S/R		D43100P	S/R			YC053-YN236, YN501-YR328
3005B	20	Y7	WE	17-3	22-12-41	D40034J	27		D43102P	9			YC051-YC052
3005B	20	Y7	WE	17-0	22-12-41	D40034P	27		D43102P	9			YC053-YD152
3005B	20	Y7	WE	17-3	22-12-41	D40034P	27		D43102P	9			YD153-YN236, YN501-YR328
3005R	20	Y7	WE	0-0	22-12-41	D40034J	26		D43102P	8			YC051-YC052
3005R	20	Y7	WE	0-0	22-12-41	D40034P	26		D43102P	8			YC053-YN236, YN501-YR328
3005Y	20	Y7	WE	0-0	22-12-41	D40034J	28		D43102P	10			YC051-YC052
3005Y	20	Y7	WE	0-0	22-12-41	D40034P	28		D43102P	10			YC053-YN236, YN501-YR328
3005Z			WE	0-0	22-12-41	D40034J	S/R		D43102P	S/R			YC051-YC052
3005Z			WE	0-0	22-12-41	D40034P	S/R		D43102P	S/R			YC053-YN236, YN501-YR328
3006B	20	Y7	WF	14-9	27-53-21	D40034J	17		D43104P	10			YC051-YC052
3006B	20	Y7	WF	14-7	27-53-21	D40034P	17		D43104P	10			YC053-YD152
3006B	20	Y7	WF	14-5	27-53-21	D40034P	17		D43104P	10			YD153-YN236, YN501-YR328
3006R	20	Y7	WF	0-0	27-53-21	D40034J	16		D43104P	9			YC051-YC052
3006R	20	Y7	WF	0-0	27-53-21	D40034P	16		D43104P	9			YC053-YN236, YN501-YR328
3006Y	20	Y7	WF	0-0	27-53-21	D40034J	18		D43104P	11			YC051-YC052
3006Y	20	Y7	WF	0-0	27-53-21	D40034P	18		D43104P	11			YC053-YN236, YN501-YR328
3006Z			WF	0-0	27-53-21	D40034J	S/R		D43104P	S/R			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W1030

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1032	286A1032			R WING TRAILNG EDGE:DISC BRACKET STA 254R TO W/W DISC & AFT CARGO DISC (continued)											
3006Z				WF	0-0	27-53-21	D40034P		S/R		D43104P		S/R		YC053-YN236, YN501-YR328
3007B	20	Y7	WG		14-9	27-53-21	D40034J	14			D43104P	13			YC051-YC052
3007B	20	Y7	WG		14-7	27-53-21	D40034P	14			D43104P	13			YC053-YD152
3007B	20	Y7	WG		14-5	27-53-21	D40034P	14			D43104P	13			YD153-YN236, YN501-YR328
3007R	20	Y7	WG		0-0	27-53-21	D40034J	13			D43104P	12			YC051-YC052
3007R	20	Y7	WG		0-0	27-53-21	D40034P	13			D43104P	12			YC053-YN236, YN501-YR328
3007Y	20	Y7	WG		0-0	27-53-21	D40034J	15			D43104P	14			YC051-YC052
3007Y	20	Y7	WG		0-0	27-53-21	D40034P	15			D43104P	14			YC053-YN236, YN501-YR328
3007Z			WG		0-0	27-53-21	D40034J		S/R		D43104P		S/R		YC051-YC052
3007Z			WG		0-0	27-53-21	D40034P		S/R		D43104P		S/R		YC053-YN236, YN501-YR328
3008B	20	Y7	WH		13-7	27-53-21	D11824	5			D43104P	17			YC051-YC052, YD153-YD158
3008B	20	Y7	WH		13-8	27-53-21	D11824	5			D43104P	17			YC053-YD152, YD160-YN236, YN501-YR328
3008R	20	Y7	WH		0-0	27-53-21	D11824	4			D43104P	16			YC051-YN236, YN501-YR328
3008Y	20	Y7	WH		0-0	27-53-21	D11824	3			D43104P	18			YC051-YN236, YN501-YR328
3008Z			WH		0-0	27-53-21	D11824		S/R		D43104P		S/R		YC051-YN236, YN501-YR328
3009B	20	Y7	WI		4-3	27-53-21	D11822	5			D43104P	21			YC051-YC052
3009B	20	Y7	WI		4-4	27-53-21	D11822	5			D43104P	21			YC053-YD152
3009B	20	Y7	WI		4-1	27-53-21	D11822	5			D43104P	21			YD153-YN236, YN501-YR328
3009R	20	Y7	WI		0-0	27-53-21	D11822	4			D43104P	20			YC051-YN236, YN501-YR328
3009Y	20	Y7	WI		0-0	27-53-21	D11822	3			D43104P	22			YC051-YN236, YN501-YR328
3009Z			WI		0-0	27-53-21	D11822		S/R		D43104P		S/R		YC051-YN236, YN501-YR328
3011B	20	Y7	WK		15-7	27-62-14	D40034J	45			D43100P	17			YC051-YC052
3011B	20	Y7	WK		15-5	27-62-14	D40034P	45			D43100P	17			YC053-YD152

WIRE LIST

D280A108

91-21-11

Section W1030

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1032	286A1032				R WING TRAILING EDGE:DISC BRACKET STA 254R TO W/W DISC & AFT CARGO DISC (continued)										
3011B	20		Y7	WK	16-5	27-62-14	D40034P	45			D43100P	17			YD153-YN236, YN501-YR328
3011R	20		Y7	WK	0-0	27-62-14	D40034J	44			D43100P	16			YC051-YC052
3011R	20		Y7	WK	0-0	27-62-14	D40034P	44			D43100P	16			YC053-YN236, YN501-YR328
3011Y	20		Y7	WK	0-0	27-62-14	D40034J	46			D43100P	18			YC051-YC052
3011Y	20		Y7	WK	0-0	27-62-14	D40034P	46			D43100P	18			YC053-YN236, YN501-YR328
3011Z				WK	0-0	27-62-14	D40034J	S/R			D43100P	S/R			YC051-YC052
3011Z				WK	0-0	27-62-14	D40034P	S/R			D43100P	S/R			YC053-YN236, YN501-YR328
W1034	286A1034				RIGHT WING TRAILING EDGE:STA 525 TO R. WING DISC STA 254R										
0513	20		HL		1-5	27-52-11	D00229	15			GD00136	ST..	E		YC051-YN236, YN501-YR328
0516	20		HL		2-3	27-62-11	D14124	5			GD01084	ST..	E		YL953-YL999, YR301-YR328
0517	20		HL		1-11	27-62-11	D14124	3			GD01086	ST..	E		YL953-YL999, YR301-YR328
0518	20		HL		2-1	27-62-11	D13964	5			GD01068	ST..	E		YL953-YL999, YR301-YR328
0519	20		HL		1-10	27-62-11	D13964	3			GD01070	ST..	E		YL953-YL999, YR301-YR328
0520	20		HL		2-1	27-62-11	D13966	5			GD01024	ST..	E		YL953-YL999, YR301-YR328
0521	20		HL		1-9	27-62-11	D13966	3			GD01026	ST..	E		YL953-YL999, YR301-YR328
0522	20		HL		2-0	27-62-11	D13968	5			GD01076	ST..	E		YL953-YL999, YR301-YR328
0523	20		HL		1-9	27-62-11	D13968	3			GD01078	ST..	E		YL953-YL999, YR301-YR328
1001	20		HP	AA	16-10	28-21-11	D00790	6			D40034P	34			YC051-YC052
1001	20		HP	AA	16-11	28-21-11	D00790	6			D40034J	34			YC053-YN236, YN501-YR328
1001Z				AA	0-0	28-21-11	D00790	S/R			D40034P	S/R			YC051-YC052
1001Z				AA	0-0	28-21-11	D00790	S/R			D40034J	S/R			YC053-YN236, YN501-YR328
1002	18		HP	AB	2-8	27-53-21	D11828	8			GD00136	ST..	E	*1	YC051-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W1030

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description		From				To				Effectivity	
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type		Splice
W1034	286A1034			RIGHT WING TRAILING EDGE:STA 525 TO R. WING DISC STA 254R (continued)											
1002Z				AB	0-0	27-53-21	D11828		S/R		GD00136	ST..	E	*1	YC051-YN236, YN501-YR328
1003	18		HP	AC	9-0	27-53-21	D11826		8		GD00134	ST..	E	*2	YC051-YC052
1003	18		HP	AC	8-11	27-53-21	D11826		8		GD00134	ST..	E	*2	YC053-YN236, YN501-YR328
1003Z				AC	0-0	27-53-21	D11826		S/R		GD00134	ST..	E	*2	YC051-YN236, YN501-YR328
2001B	20		Y6	GA	27-9	27-18-11	D03574		1		D40034P		7		YC051-YC052
2001B	20		Y6	GA	28-0	27-18-11	D03574		1		D40034J		7		YC053-YD158, YN231
2001B	20		Y6	GA	28-1	27-18-11	D03574		1		D40034J		7		YD160-YL954, YN232-YN235
2001B	20		Y6	GA	27-11	27-18-11	D03574		1		D40034J		7		YL955-YL968, YN236, YN501-YR301
2001B	20		Y6	GA	27-10	27-18-11	D03574		1		D40034J		7		YL969-YL999, YR303-YR328
2001R	20		Y6	GA	0-0	27-18-11	D03574		2		D40034P		6		YC051-YC052
2001R	20		Y6	GA	0-0	27-18-11	D03574		2		D40034J		6		YC053-YN236, YN501-YR328
2001Z				GA	0-0	27-18-11	GD00130	ST..	E		D40034P	S/R			YC051-YC052
2001Z				GA	0-0	27-18-11	GD00130	ST..	E		D40034J	S/R			YC053-YN236, YN501-YR328
2002B	20		Y6	GB	12-9	22-11-31	D01697		2		D40034P		2		YC051-YC052
2002B	20		Y6	GB	13-1	22-11-31	D01697		2		D40034J		2		YC053-YL968, YN231-YN236, YN501-YR301
2002B	20		Y6	GB	12-11	22-11-31	D01697		2		D40034J		2		YL969-YL999, YR303-YR328
2002R	20		Y6	GB	0-0	22-11-31	D01697		1		D40034P		1		YC051-YC052
2002R	20		Y6	GB	0-0	22-11-31	D01697		1		D40034J		1		YC053-YN236, YN501-YR328
2002Z				GB	0-0	22-11-31	D01697		S/R		D40034P	S/R			YC051-YC052
2002Z				GB	0-0	22-11-31	D01697		S/R		D40034J	S/R			YC053-YN236, YN501-YR328
2003B	20		Y6	GC	13-0	22-11-31	D01701		2		D40034P		20		YC051-YC052
2003B	20		Y6	GC	13-1	22-11-31	D01701		2		D40034J		20		YC053-YD158, YN231
2003B	20		Y6	GC	12-11	22-11-31	D01701		2		D40034J		20		YD160-YL968, YN232-YN236, YN501-YR301

WIRE LIST
D280A108

91-21-11
Section W1030
Page 9
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1034	286A1034			RIGHT WING TRAILING EDGE:STA 525 TO R. WING DISC STA 254R (continued)											
2003B	20	Y6	GC		12-9	22-11-31	D01701		2		D40034J	20			YL969-YL999, YR303-YR328
2003R	20	Y6	GC		0-0	22-11-31	D01701		1		D40034P	19			YC051-YC052
2003R	20	Y6	GC		0-0	22-11-31	D01701		1		D40034J	19			YC053-YN236, YN501-YR328
2003Z			GC		0-0	22-11-31	D01701		S/R		D40034P	S/R			YC051-YC052
2003Z			GC		0-0	22-11-31	D01701		S/R		D40034J	S/R			YC053-YN236, YN501-YR328
2004B	20	Y6	GD		20-10	27-32-11	D00229		5		D40034P	30			YC051-YC052
2004B	20	Y6	GD		20-10	27-32-11	D00229		5		D40034J	30			YC053-YL968, YN231-YN236, YN501-YR301
2004B	20	Y6	GD		20-9	27-32-11	D00229		5		D40034J	30			YL969-YL999, YR303-YR328
2004R	20	Y6	GD		0-0	27-32-11	D00229		4		D40034P	29			YC051-YC052
2004R	20	Y6	GD		0-0	27-32-11	D00229		4		D40034J	29			YC053-YN236, YN501-YR328
2004Z			GD		0-0	27-32-11	D00229		S/R		D40034P	S/R			YC051-YC052
2004Z			GD		0-0	27-32-11	D00229		S/R		D40034J	S/R			YC053-YN236, YN501-YR328
2005B	20	Y6	GE		20-10	22-11-11	D00229		10		D40034P	25			YC051-YC052
2005B	20	Y6	GE		20-10	22-11-11	D00229		10		D40034J	25			YC053-YL968, YN231-YN236, YN501-YR301
2005B	20	Y6	GE		20-9	22-11-11	D00229		10		D40034J	25			YL969-YL999, YR303-YR328
2005R	20	Y6	GE		0-0	22-11-11	D00229		9		D40034P	24			YC051-YC052
2005R	20	Y6	GE		0-0	22-11-11	D00229		9		D40034J	24			YC053-YN236, YN501-YR328
2005Z			GE		0-0	22-11-11	D00229		S/R		D40034P	S/R			YC051-YC052
2005Z			GE		0-0	22-11-11	D00229		S/R		D40034J	S/R			YC053-YN236, YN501-YR328
2006B	20	M2	GF		20-10	27-52-11	D00229		2		D40034P	37			YC051-YC052
2006B	20	M2	GF		20-10	27-52-11	D00229		2		D40034J	37			YC053-YL968, YN231-YN236, YN501-YR301
2006B	20	M2	GF		20-9	27-52-11	D00229		2		D40034J	37			YL969-YL999, YR303-YR328
2006R	20	M2	GF		0-0	27-52-11	D00229		1		D40034P	36			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W1030

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1034	286A1034				RIGHT WING TRAILING EDGE:STA 525 TO R. WING DISC STA 254R (continued)										
2006R	20		M2	GF	0-0	27-52-11	D00229		1		D40034J	36			YC053-YN236, YN501-YR328
2006ZI				GF	0-0	27-52-11	D00229		S/R		D40034P	38			YC051-YC052
2006ZI				GF	0-0	27-52-11	D00229		S/R		D40034J	38			YC053-YN236, YN501-YR328
2006ZO				GF	0-0	27-52-11	D00229		S/R		D40034P	S/R			YC051-YC052
2006ZO				GF	0-0	27-52-11	D00229		S/R		D40034J	S/R			YC053-YN236, YN501-YR328
2007B	20		M2	GG	20-10	27-52-11	D00229		3		D40034P	41			YC051-YC052
2007B	20		M2	GG	20-10	27-52-11	D00229		3		D40034J	41			YC053-YL968, YN231-YN236, YN501-YR301
2007B	20		M2	GG	20-9	27-52-11	D00229		3		D40034J	41			YL969-YL999, YR303-YR328
2007R	20		M2	GG	0-0	27-52-11	D00229		11		D40034P	40			YC051-YC052
2007R	20		M2	GG	0-0	27-52-11	D00229		11		D40034J	40			YC053-YN236, YN501-YR328
2007ZI				GG	0-0	27-52-11	D00229		S/R		D40034P	39			YC051-YC052
2007ZI				GG	0-0	27-52-11	D00229		S/R		D40034J	39			YC053-YN236, YN501-YR328
2007ZO				GG	0-0	27-52-11	D00229		S/R		D40034P	S/R			YC051-YC052
2007ZO				GG	0-0	27-52-11	D00229		S/R		D40034J	S/R			YC053-YN236, YN501-YR328
2008B	20		Y6	GI	18-6	27-53-21	D11826		7		D11828	1			YC051-YC052
2008B	20		Y6	GI	18-5	27-53-21	D11826		7		D11828	1			YC053-YD158, YN231
2008B	20		Y6	GI	18-4	27-53-21	D11826		7		D11828	1			YD160-YL999, YN232-YN236, YN501-YR328
2008R	20		Y6	GI	0-0	27-53-21	D11826		6		D11828	2			YC051-YN236, YN501-YR328
2008Z				GI	0-0	27-53-21	D11826		S/R		D11828	S/R			YC051-YN236, YN501-YR328
2009B	20		Y6	GH	11-10	27-53-21	D11826		1		D40034P	12			YC051-YC052
2009B	20		Y6	GH	11-10	27-53-21	D11826		1		D40034J	12			YC053-YD158, YN231
2009B	20		Y6	GH	11-11	27-53-21	D11826		1		D40034J	12			YD160-YL968, YN232-YN236, YN501-YR301
2009B	20		Y6	GH	11-9	27-53-21	D11826		1		D40034J	12			YL969-YL999, YR303-YR328

WIRE LIST
D280A108

91-21-11
Section W1030
Page 11
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1034	286A1034				RIGHT WING TRAILING EDGE:STA 525 TO R. WING DISC STA 254R (continued)										
2009R	20	Y6	GH		0-0	27-53-21	D11826		2		D40034P	11			YC051-YC052
2009R	20	Y6	GH		0-0	27-53-21	D11826		2		D40034J	11			YC053-YN236, YN501-YR328
2009Z			GH		0-0	27-53-21	D11826		S/R		D40034P	S/R			YC051-YC052
2009Z			GH		0-0	27-53-21	D11826		S/R		D40034J	S/R			YC053-YN236, YN501-YR328
2011B	20	Y6	GK		11-10	27-62-14	D10541		1		D40034P	43			YC051-YC052
2011B	20	Y6	GK		12-0	27-62-14	D10541		1		D40034J	43			YC053-YL968, YN231-YN236, YN501-YR301
2011B	20	Y6	GK		11-10	27-62-14	D10541		1		D40034J	43			YL969-YL999, YR303-YR328
2011R	20	Y6	GK		0-0	27-62-14	D10541		2		D40034P	42			YC051-YC052
2011R	20	Y6	GK		0-0	27-62-14	D10541		2		D40034J	42			YC053-YN236, YN501-YR328
2011Z			GK		0-0	27-62-14	GD00132	ST..	E		D40034P	S/R			YC051-YC052
2011Z			GK		0-0	27-62-14	GD00132	ST..	E		D40034J	S/R			YC053-YN236, YN501-YR328
2012B	20	Y6	OL		7-11	27-62-11	D14124		4		D40034J	48			YL953-YL968, YR301
2012B	20	Y6	OL		7-10	27-62-11	D14124		4		D40034J	48			YL969-YL999, YR303-YR328
2012R	20	Y6	OL		0-0	27-62-11	D14124		1		D40034J	47			YL953-YL999, YR301-YR328
2012Z			OL		0-0	27-62-11	D14124		S/R		D40034J	S/R			YL953-YL999, YR301-YR328
2013B	20	Y6	OM		11-4	27-62-11	D13964		4		D40034J	50			YL953-YL968, YR301
2013B	20	Y6	OM		11-2	27-62-11	D13964		4		D40034J	50			YL969-YL999, YR303-YR328
2013R	20	Y6	OM		0-0	27-62-11	D13964		1		D40034J	49			YL953-YL999, YR301-YR328
2013Z			OM		0-0	27-62-11	D13964		S/R		D40034J	S/R			YL953-YL999, YR301-YR328
2014B	20	Y6	ON		14-10	27-62-11	D13966		4		D40034J	52			YL953-YL968, YR301
2014B	20	Y6	ON		14-9	27-62-11	D13966		4		D40034J	52			YL969-YL999, YR303-YR328
2014R	20	Y6	ON		0-0	27-62-11	D13966		1		D40034J	51			YL953-YL999, YR301-YR328
2014Z			ON		0-0	27-62-11	D13966		S/R		D40034J	S/R			YL953-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W1030

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1034	286A1034				RIGHT WING TRAILING EDGE:STA 525 TO R. WING DISC STA 254R (continued)										
2015B	20	Y6	OP		17-2	27-62-11	D13968		4		D40034J	54			YL953-YL968, YR301
2015B	20	Y6	OP		17-1	27-62-11	D13968		4		D40034J	54			YL969-YL999, YR303-YR328
2015R	20	Y6	OP		0-0	27-62-11	D13968		1		D40034J	53			YL953-YL999, YR301-YR328
2015Z			OP		0-0	27-62-11	D13968		S/R		D40034J	S/R			YL953-YL999, YR301-YR328
3001B	20	Y7	WA		27-9	27-18-11	D03574		5		D40034P	9			YC051-YC052
3001B	20	Y7	WA		28-0	27-18-11	D03574		5		D40034J	9			YC053-YD158, YN231
3001B	20	Y7	WA		28-1	27-18-11	D03574		5		D40034J	9			YD160-YL954, YN232-YN235
3001B	20	Y7	WA		27-11	27-18-11	D03574		5		D40034J	9			YL955-YL968, YN236, YN501-YR301
3001B	20	Y7	WA		27-10	27-18-11	D03574		5		D40034J	9			YL969-YL999, YR303-YR328
3001R	20	Y7	WA		0-0	27-18-11	D03574		4		D40034P	8			YC051-YC052
3001R	20	Y7	WA		0-0	27-18-11	D03574		4		D40034J	8			YC053-YN236, YN501-YR328
3001Y	20	Y7	WA		0-0	27-18-11	D03574		3		D40034P	10			YC051-YC052
3001Y	20	Y7	WA		0-0	27-18-11	D03574		3		D40034J	10			YC053-YN236, YN501-YR328
3001Z			WA		0-0	27-18-11	GD00130	ST..	E		D40034P	S/R			YC051-YC052
3001Z			WA		0-0	27-18-11	GD00130	ST..	E		D40034J	S/R			YC053-YN236, YN501-YR328
3002B	20	Y7	WB		12-9	22-11-31	D01697		5		D40034P	4			YC051-YC052
3002B	20	Y7	WB		13-1	22-11-31	D01697		5		D40034J	4			YC053-YL968, YN231-YN236, YN501-YR301
3002B	20	Y7	WB		12-11	22-11-31	D01697		5		D40034J	4			YL969-YL999, YR303-YR314
3002B	20	Y6	WB		12-11	22-11-31	D01697		5		D40034J	4			YR315-YR328
3002R	20	Y7	WB		0-0	22-11-31	D01697		4		D40034P	3			YC051-YC052
3002R	20	Y7	WB		0-0	22-11-31	D01697		4		D40034J	3			YC053-YN236, YN501-YR314
3002R	20	Y6	WB		0-0	22-11-31	D01697		4		D40034J	3			YR315-YR328
3002Y	20	Y7	WB		0-0	22-11-31	D01697		3		D40034P	5			YC051-YC052
3002Y	20	Y7	WB		0-0	22-11-31	D01697		3		D40034J	5			YC053-YN236, YN501-YR314
3002Z			WB		0-0	22-11-31	D01697		S/R		D40034P	S/R			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W1030

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W1034	286A1034			RIGHT WING TRAILING EDGE:STA 525 TO R. WING DISC STA 254R (continued)										
3002Z				WB	0-0	22-11-31	D01697	S/R		D40034J	S/R		YC053-YN236, YN501-YR328	
3003B	20	Y7	WC		13-0	22-11-31	D01701	5		D40034P	22		YC051-YC052	
3003B	20	Y7	WC		13-1	22-11-31	D01701	5		D40034J	22		YC053-YD158, YN231	
3003B	20	Y7	WC		12-11	22-11-31	D01701	5		D40034J	22		YD160-YL968, YN232-YN236, YN501-YR301	
3003B	20	Y7	WC		12-9	22-11-31	D01701	5		D40034J	22		YL969-YL999, YR303-YR314	
3003B	20	Y6	WC		12-9	22-11-31	D01701	5		D40034J	22		YR315-YR328	
3003R	20	Y7	WC		0-0	22-11-31	D01701	4		D40034P	21		YC051-YC052	
3003R	20	Y7	WC		0-0	22-11-31	D01701	4		D40034J	21		YC053-YN236, YN501-YR314	
3003R	20	Y6	WC		0-0	22-11-31	D01701	4		D40034J	21		YR315-YR328	
3003Y	20	Y7	WC		0-0	22-11-31	D01701	3		D40034P	23		YC051-YC052	
3003Y	20	Y7	WC		0-0	22-11-31	D01701	3		D40034J	23		YC053-YN236, YN501-YR314	
3003Z				WC	0-0	22-11-31	D01701	S/R		D40034P	S/R		YC051-YC052	
3003Z				WC	0-0	22-11-31	D01701	S/R		D40034J	S/R		YC053-YN236, YN501-YR328	
3004B	20	Y7	WD		20-10	27-32-11	D00229	7		D40034P	32		YC051-YC052	
3004B	20	Y7	WD		20-10	27-32-11	D00229	7		D40034J	32		YC053-YL968, YN231-YN236, YN501-YR301	
3004B	20	Y7	WD		20-9	27-32-11	D00229	7		D40034J	32		YL969-YL999, YR303-YR328	
3004R	20	Y7	WD		0-0	27-32-11	D00229	6		D40034P	31		YC051-YC052	
3004R	20	Y7	WD		0-0	27-32-11	D00229	6		D40034J	31		YC053-YN236, YN501-YR328	
3004Y	20	Y7	WD		0-0	27-32-11	D00229	8		D40034P	33		YC051-YC052	
3004Y	20	Y7	WD		0-0	27-32-11	D00229	8		D40034J	33		YC053-YN236, YN501-YR328	
3004Z				WD	0-0	27-32-11	D00229	S/R		D40034P	S/R		YC051-YC052	
3004Z				WD	0-0	27-32-11	D00229	S/R		D40034J	S/R		YC053-YN236, YN501-YR328	
3005B	20	Y7	WE		20-10	22-12-41	D00229	13		D40034P	27		YC051-YC052	
3005B	20	Y7	WE		20-10	22-12-41	D00229	13		D40034J	27		YC053-YL968, YN231-YN236, YN501-YR301	

WIRE LIST

D280A108

91-21-11

Section W1030

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1034	286A1034				RIGHT WING TRAILING EDGE:STA 525 TO R. WING DISC STA 254R (continued)										
3005B	20	Y7	WE		20-9	22-12-41	D00229		13		D40034J	27			YL969-YL999, YR303-YR328
3005R	20	Y7	WE		0-0	22-12-41	D00229		12		D40034P	26			YC051-YC052
3005R	20	Y7	WE		0-0	22-12-41	D00229		12		D40034J	26			YC053-YN236, YN501-YR328
3005Y	20	Y7	WE		0-0	22-12-41	D00229		14		D40034P	28			YC051-YC052
3005Y	20	Y7	WE		0-0	22-12-41	D00229		14		D40034J	28			YC053-YN236, YN501-YR328
3005Z			WE		0-0	22-12-41	D00229		S/R		D40034P	S/R			YC051-YC052
3005Z			WE		0-0	22-12-41	D00229		S/R		D40034J	S/R			YC053-YN236, YN501-YR328
3006B	20	Y7	WF		22-6	27-53-21	D11828		5		D40034P	17			YC051-YC052
3006B	20	Y7	WF		22-7	27-53-21	D11828		5		D40034J	17			YC053-YL968, YN231-YN236, YN501-YR301
3006B	20	Y7	WF		22-5	27-53-21	D11828		5		D40034J	17			YL969-YL999, YR303-YR328
3006R	20	Y7	WF		0-0	27-53-21	D11828		4		D40034P	16			YC051-YC052
3006R	20	Y7	WF		0-0	27-53-21	D11828		4		D40034J	16			YC053-YN236, YN501-YR328
3006Y	20	Y7	WF		0-0	27-53-21	D11828		3		D40034P	18			YC051-YC052
3006Y	20	Y7	WF		0-0	27-53-21	D11828		3		D40034J	18			YC053-YN236, YN501-YR328
3006Z			WF		0-0	27-53-21	D11828		S/R		D40034P	S/R			YC051-YC052
3006Z			WF		0-0	27-53-21	D11828		S/R		D40034J	S/R			YC053-YN236, YN501-YR328
3007B	20	Y7	WG		11-10	27-53-21	D11826		5		D40034P	14			YC051-YC052
3007B	20	Y7	WG		11-10	27-53-21	D11826		5		D40034J	14			YC053-YD158, YN231
3007B	20	Y7	WG		11-11	27-53-21	D11826		5		D40034J	14			YD160-YL968, YN232-YN236, YN501-YR301
3007B	20	Y7	WG		11-9	27-53-21	D11826		5		D40034J	14			YL969-YL999, YR303-YR328
3007R	20	Y7	WG		0-0	27-53-21	D11826		4		D40034P	13			YC051-YC052
3007R	20	Y7	WG		0-0	27-53-21	D11826		4		D40034J	13			YC053-YN236, YN501-YR328
3007Y	20	Y7	WG		0-0	27-53-21	D11826		3		D40034P	15			YC051-YC052
3007Y	20	Y7	WG		0-0	27-53-21	D11826		3		D40034J	15			YC053-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W1030

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1034	286A1034			RIGHT WING TRAILING EDGE:STA 525 TO R. WING DISC STA 254R (continued)											
3007Z				WG	0-0	27-53-21	D11826		S/R		D40034P		S/R		YC051-YC052
3007Z				WG	0-0	27-53-21	D11826		S/R		D40034J		S/R		YC053-YN236, YN501-YR328
3011B	20		Y7	WK	11-10	27-62-14	D10541		5		D40034P		45		YC051-YC052
3011B	20		Y7	WK	12-0	27-62-14	D10541		5		D40034J		45		YC053-YL968, YN231-YN236, YN501-YR301
3011B	20		Y7	WK	11-10	27-62-14	D10541		5		D40034J		45		YL969-YL999, YR303-YR328
3011R	20		Y7	WK	0-0	27-62-14	D10541		4		D40034P		44		YC051-YC052
3011R	20		Y7	WK	0-0	27-62-14	D10541		4		D40034J		44		YC053-YN236, YN501-YR328
3011Y	20		Y7	WK	0-0	27-62-14	D10541		3		D40034P		46		YC051-YC052
3011Y	20		Y7	WK	0-0	27-62-14	D10541		3		D40034J		46		YC053-YN236, YN501-YR328
3011Z				WK	0-0	27-62-14	GD00132		ST..	E	D40034P		S/R		YC051-YC052
3011Z				WK	0-0	27-62-14	GD00132		ST..	E	D40034J		S/R		YC053-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W1030

Page 16 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1062	286A1062			ENGINE POWER FEEDER											
0001	02	HA		7-3	24-21-11	G00009		T1	R		D30038	A			ALL
0002	02	HA		7-3	24-21-11	G00009		T2	R		D30038	B			ALL
0003	02	HA		7-3	24-21-11	G00009		T3	R		D30038	C			ALL
0004	04	HA		7-3	24-21-11	G00009		N	R		D30038	D			ALL

WIRE LIST

D280A108

91-21-11

Section W1060

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To					
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W1080	286A1080			ENGINE-THRUST REVERSER LEFT SLEEVE CH-A												
2002B	20		HX	AB	2-1	78-35-11	D30002			9		D30072		2		YC056-YC058
2002B	20		E5	AB	2-1	78-35-11	D30002			9		D30072		2		YC059-YD157
2002B	20		E5	AB	2-2	78-35-11	D30002			9		D30072		2		YD158-YR328
2002R	20		HX	AB	0-0	78-35-11	D30002			10		D30072		1		YC056-YC058
2002R	20		E5	AB	0-0	78-35-11	D30002			10		D30072		1		YC059-YR328
2002Z				AB	0-0	78-35-11	D30002		PERB			D30072		PERB		YC056-YR328
3001B	20		HY	AC	2-1	78-35-11	D30002			5		D30072		4		YC056-YC058
3001B	20		E6	AC	2-1	78-35-11	D30002			5		D30072		4		YC059-YD157
3001B	20		E6	AC	2-2	78-35-11	D30002			5		D30072		4		YD158-YR328
3001R	20		HY	AC	0-0	78-35-11	D30002			6		D30072		3		YC056-YC058
3001R	20		E6	AC	0-0	78-35-11	D30002			6		D30072		3		YC059-YR328
3001Y	20		HY	AC	0-0	78-35-11	D30002			4		D30072		5		YC056-YC058
3001Y	20		E6	AC	0-0	78-35-11	D30002			4		D30072		5		YC059-YR328
3001Z				AC	0-0	78-35-11	D30002		PERB			D30072		PERB		YC056-YR328
3002B	18		HR	AA	9-3	78-32-61	D30002			12		D01008		2		YC056-YC058
3002B	18		E6	AA	9-3	78-32-61	D30002			12		D01008		2		YC059-YR328
3002R	18		HR	AA	0-0	78-32-61	D30002			3		D01008		1		YC056-YC058
3002R	18		E6	AA	0-0	78-32-61	D30002			3		D01008		1		YC059-YR328
3002Y	18		HR	AA	0-0	78-32-61	D30002			13		D01008		3		YC056-YC058
3002Y	18		E6	AA	0-0	78-32-61	D30002			13		D01008		3		YC059-YR328
3002Z				AA	0-0	78-32-61	D30002		PERB			D01008		PERB		YC056-YR328
A-B				AD	0-0	78-36-11	D30002			8		S00831		BLU		YC056-YR328
A-R				AD	0-0	78-36-11	D30002			7		S00831		RED		YC056-YR328
A-Y				AD	0-0	78-36-11	D30002			1		S00831		YEL		YC056-YR328
A-Z				AD	0-0	78-36-11	D30002		PERB			S00831		GND		YC056-YR328
YAAA					0-0	78-35-11	D30002		PERB			OAS0001		PERB		YC056-YR328
YAAB					0-0	78-35-11	D30072		PERB			OAS0001		PERB		YC056-YR328
YAAC					0-0	78-32-51	D01008		PERB			OAS0002		PERB		YC056-YR328
YAAD					0-0	78-36-11	S00831		PERB			OAS0002		PERB		YC056-YR328
YAAE					0-0	78-35-11	OAS0001		PERB			OAS0002		PERB		YC056-YR328
W1082	286A1082			ENGINE-THRUST REVERSER LEFT SLEEVE CH-B												
2001B	20		HX	AA	2-7	78-35-11	D30008			7		D30076		2		YC056-YC058
2001B	20		E5	AA	2-7	78-35-11	D30008			7		D30076		2		YC059-YD157
2001B	20		E5	AA	2-8	78-35-11	D30008			7		D30076		2		YD158-YR328
2001R	20		HX	AA	0-0	78-35-11	D30008			6		D30076		1		YC056-YC058
2001R	20		E5	AA	0-0	78-35-11	D30008			6		D30076		1		YC059-YR328
2001Z				AA	0-0	78-35-11	D30008		PERB			D30076		PERB		YC056-YR328
3001B	20		HY	AB	2-7	78-35-11	D30008			2		D30076		4		YC056-YC058

WIRE LIST

D280A108

91-21-11

Section W1080

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1082	286A1082			ENGINE-THRUST REVERSER LEFT SLEEVE CH-B (continued)											
3001B	20	E6	AB		2-7	78-35-11	D30008		2		D30076		4		YC059-YD157
3001B	20	E6	AB		2-8	78-35-11	D30008		2		D30076		4		YD158-YR328
3001R	20	HY	AB		0-0	78-35-11	D30008		3		D30076		3		YC056-YC058
3001R	20	E6	AB		0-0	78-35-11	D30008		3		D30076		3		YC059-YR328
3001Y	20	HY	AB		0-0	78-35-11	D30008		10		D30076		5		YC056-YC058
3001Y	20	E6	AB		0-0	78-35-11	D30008		10		D30076		5		YC059-YR328
3001Z			AB		0-0	78-35-11	D30008		PERB		D30076		PERB		YC056-YR328
A-B			AC		0-0	78-36-11	D30008		5		S00835		BLU		YC056-YR328
A-R			AC		0-0	78-36-11	D30008		4		S00835		RED		YC056-YR328
A-Y			AC		0-0	78-36-11	D30008		1		S00835		YEL		YC056-YR328
A-Z			AC		0-0	78-36-11	D30008		PERB		S00835		GND		YC056-YR328
YAAA					0-0	78-35-21	D30008		PERB		OAS0001		PERB		YC056-YR328
YAAB					0-0	78-35-11	D30076		PERB		OAS0001		PERB		YC056-YR328
YAAC					0-0	78-36-11	S00835		PERB		OAS0001		PERB		YC056-YR328
W1084	286A1084			ENGINE-THRUST REVERSER RIGHT SLEEVE CH-B											
2001B	20	HX	AA		2-11	78-35-11	D30010		7		D30078		2		YC056-YC058
2001B	20	E5	AA		3-1	78-35-11	D30010		7		D30078		2		YC059-YR328
2001R	20	HX	AA		0-0	78-35-11	D30010		6		D30078		1		YC056-YC058
2001R	20	E5	AA		0-0	78-35-11	D30010		6		D30078		1		YC059-YR328
2001Z			AA		0-0	78-35-11	D30010		PERB		D30078		PERB		YC056-YR328
3001B	20	HY	AB		2-11	78-35-11	D30010		2		D30078		4		YC056-YC058
3001B	20	E6	AB		3-1	78-35-11	D30010		2		D30078		4		YC059-YR328
3001R	20	HY	AB		0-0	78-35-11	D30010		3		D30078		3		YC056-YC058
3001R	20	E6	AB		0-0	78-35-11	D30010		3		D30078		3		YC059-YR328
3001Y	20	HY	AB		0-0	78-35-11	D30010		10		D30078		5		YC056-YC058
3001Y	20	E6	AB		0-0	78-35-11	D30010		10		D30078		5		YC059-YR328
3001Z			AB		0-0	78-35-11	D30010		PERB		D30078		PERB		YC056-YR328
A-B			AC		0-0	78-36-11	D30010		5		S00836		BLU		YC056-YR328
A-R			AC		0-0	78-36-11	D30010		4		S00836		RED		YC056-YR328
A-Y			AC		0-0	78-36-11	D30010		1		S00836		YEL		YC056-YR328
A-Z			AC		0-0	78-36-11	D30010		PERB		S00836		GND		YC056-YR328
YAAA					0-0	78-35-11	D30010		PERB		OAS0001		PERB		YC056-YR328
YAAB					0-0	78-35-11	D30078		PERB		OAS0001		PERB		YC056-YR328
YAAC					0-0	78-36-11	S00836		PERB		OAS0001		PERB		YC056-YR328
W1086	286A1086			ENGINE-THRUST REVERSER RIGHT SLEEVE CH-A											
2002B	20	HX	AB		3-1	78-35-11	D30074		2		D30006		9		YC056-YC058
2002B	20	E5	AB		3-1	78-35-11	D30074		2		D30006		9		YC059-YR328

WIRE LIST

D280A108

91-21-11

Section W1080

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1086		286A1086			ENGINE-THRUST REVERSER RIGHT SLEEVE CH-A (continued)											
2002R		20		HX	AB	0-0	78-35-11	D30074		1		D30006		10		YC056-YC058
2002R		20		E5	AB	0-0	78-35-11	D30074		1		D30006		10		YC059-YR328
2002Z					AB	0-0	78-35-11	D30074		PERB		D30006		PERB		YC056-YR328
3001B		20		HY	AC	3-1	78-35-11	D30074		4		D30006		5		YC056-YC058
3001B		20		E6	AC	3-1	78-35-11	D30074		4		D30006		5		YC059-YR328
3001R		20		HY	AC	0-0	78-35-11	D30074		3		D30006		6		YC056-YC058
3001R		20		E6	AC	0-0	78-35-11	D30074		3		D30006		6		YC059-YR328
3001Y		20		HY	AC	0-0	78-35-11	D30074		5		D30006		4		YC056-YC058
3001Y		20		E6	AC	0-0	78-35-11	D30074		5		D30006		4		YC059-YR328
3001Z					AC	0-0	78-35-11	D30074		PERB		D30006		PERB		YC056-YR328
3002B		18		HR	AA	9-5	78-32-61	D01016		2		D30006		12		YC056-YC058
3002B		18		E6	AA	9-5	78-32-61	D01016		2		D30006		12		YC059-YR328
3002R		18		HR	AA	0-0	78-32-61	D01016		1		D30006		3		YC056-YC058
3002R		18		E6	AA	0-0	78-32-61	D01016		1		D30006		3		YC059-YR328
3002Y		18		HR	AA	0-0	78-32-61	D01016		3		D30006		13		YC056-YC058
3002Y		18		E6	AA	0-0	78-32-61	D01016		3		D30006		13		YC059-YR328
3002Z					AA	0-0	78-32-61	D01016		PERB		D30006		PERB		YC056-YR328
A-B					AD	0-0	78-36-11	S00832		BLU		D30006		8		YC056-YR328
A-R					AD	0-0	78-36-11	S00832		RED		D30006		7		YC056-YR328
A-Y					AD	0-0	78-36-11	S00832		YEL		D30006		1		YC056-YR328
A-Z					AD	0-0	78-36-11	S00832		GND		D30006		PERB		YC056-YR328
YAAA						0-0	78-35-11	D30006		PERB		OAS0001		PERB		YC056-YR328
YAAB						0-0	78-35-11	D30074		PERB		OAS0001		PERB		YC056-YR328
YAAC						0-0	78-32-51	D01016		PERB		OAS0002		PERB		YC056-YR328
YAAD						0-0	78-36-11	S00832		PERB		OAS0002		PERB		YC056-YR328
YAAE						0-0	78-35-11	OAS0001		PERB		OAS0002		PERB		YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W1080

Page 3 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1126	286A1126				CENTER TANK R FUEL BOOST PUMP TO AB0500DR										
1303	20	VF	EQ		24-0	28-43-11	D00878		3		D41850P		1		YC051-YD158
1303	20	VF	EQ		24-2	28-43-11	D00878		3		D41850P		1		YL951-YR328
1303Z			EQ		0-0	28-43-11	D00878		DED		D41850P		DED		YC051-YD158, YL951-YR328
1304	20	VF	ER		2-0	28-43-11	D00878		2		GD00314		DC..	E	YC051-YD152, YL964-YL999, YN236-YR328
1304	20	VF	ER		1-11	28-43-11	D00878		2		GD00314		DC..	E	YD153-YD158
1304	20	VF	ER		2-1	28-43-11	D00878		2		GD00314		DC..	E	YL951-YL963, YN231-YN235
1304Z				ER	0-0	28-43-11	D00878		DED		GD00314		DED		YC051-YD158, YL951-YR328
1305	20	VF	ES		22-9	28-22-11	D00792		3		D41850P		5		YC051-YD152
1305	20	VF	ES		22-6	28-22-11	D00792		3		D41850P		5		YD153-YD158, YL951-YR328
1305Z				ES	0-0	28-22-11	D00792		DED		D41850P		DED		YC051-YD158, YL951-YR328
1306	20	VF	ET		22-9	28-22-11	D00792		2		D41850P		6		YC051-YD152
1306	20	VF	ET		22-6	28-22-11	D00792		2		D41850P		6		YD153-YD158, YL951-YR328
1306Z				ET	0-0	28-22-11	D00792		DED		D41850P		DED		YC051-YD158, YL951-YR328
1307	18	VF	EU		4-6	28-22-11	D00792		7		GD00190		ST..	E	YC051-YD152
1307	18	VF	EU		3-10	28-22-11	D00792		7		GD00190		ST..	E	YD153-YD158, YL951-YL963, YN231-YN235
1307	18	VF	EU		3-9	28-22-11	D00792		7		GD00190		ST..	E	YL964-YL999, YN236-YR328
1307Z				EU	0-0	28-22-11	D00792		DED		GD00190		DED		YC051-YD158, YL951-YR328
1308	18	VF	EV		2-7	28-22-11	D00792		4		GD00324		DC..	E	YC051-YD152
1308	18	VF	EV		3-1	28-22-11	D00792		4		GD00324		DC..	E	YD153-YD158, YL951-YR328
1308Z				EV	0-0	28-22-11	D00792		DED		GD00324		DED		YC051-YD158, YL951-YR328
1309	20	VF	EW		22-9	28-22-11	D00792		5		D41850P		7		YC051-YD152
1309	20	VF	EW		22-6	28-22-11	D00792		5		D41850P		7		YD153-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W1120

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W1126	286A1126	CENTER TANK R FUEL BOOST PUMP TO AB0500DR (continued)													
1309Z		EW	0-0	28-22-11	D00792	DED			D41850P	DED				YC051-YD158, YL951-YR328	
3601B	18	VH A4	25-1	28-23-11	D05350P	13			D00804	3				YC051-YD152	
3601B	18	VH A4	24-11	28-23-11	D05350P	13			D00804	3				YD153-YD158, YL951-YR328	
3601R	18	VH A4	0-0	28-23-11	D05350P	11			D00804	1				YC051-YD158, YL951-YR328	
3601Y	18	VH A4	0-0	28-23-11	D05350P	12			D00804	2				YC051-YD158, YL951-YR328	
3601Z		A4	0-0	28-23-11	D05350P	DED			D00804	DED				YC051-YD158, YL951-YR328	
W1128	286A1128	CENTER TANK L FUEL BOOST PUMP TO AB0500DL													
1301	20	VF EN	25-7	28-43-11	D00876	3			D41854P	1				YC051-YC055	
1301	20	VF EN	25-5	28-43-11	D00876	3			D41854P	1				YC056-YD152	
1301	20	VF EN	24-8	28-43-11	D00876	3			D41854P	1				YD153-YD158, YL951-YN236, YN501-YR313	
1301	20	VF EN	24-4	28-43-11	D00876	3			D41854P	1				YR314-YR328	
1301Z		EN	0-0	28-43-11	D00876	DED			D41854P	DED				YC051-YD158, YL951-YN236, YN501-YR328	
1302	20	VF EP	2-9	28-43-11	D00876	2			GD00320	DC..	E			YC051-YC055, YR314-YR328	
1302	20	VF EP	2-7	28-43-11	D00876	2			GD00320	DC..	E			YC056-YD152	
1302	20	VF EP	3-1	28-43-11	D00876	2			GD00320	DC..	E			YD153-YD158, YL951-YN236, YN501-YR313	
1302Z		EP	0-0	28-43-11	D00876	DED			GD00320	DED				YC051-YD158, YL951-YN236, YN501-YR328	
3601B	18	VH A4	26-2	28-23-11	D05348P	2			D00802	3				YC051-YC055	
3601B	18	VH A4	25-11	28-23-11	D05348P	2			D00802	3				YC056-YD152	
3601B	18	VH A4	25-4	28-23-11	D05348P	2			D00802	3				YD153-YD157, YL951-YN236, YN501-YR328	
3601B	18	VH A4	25-1	28-23-11	D05348P	2			D00802	3				YD158	

WIRE LIST

D280A108

91-21-11

Section W1120

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1128	286A1128					CENTER TANK L FUEL BOOST PUMP TO AB0500DL (continued)									
3601R	18	VH	A4		0-0	28-23-11	D05348P	4			D00802	1			YC051-YD158, YL951-YN236, YN501-YR328
3601Y	18	VH	A4		0-0	28-23-11	D05348P	3			D00802	2			YC051-YD158, YL951-YN236, YN501-YR328
3601Z			A4		0-0	28-23-11	D05348P	DED			D00802	DED			YC051-YD158, YL951-YN236, YN501-YR328

WIRE LIST
D280A108

91-21-11
Section W1120
Page 3 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1134		286A1134			NO.2 AFT BOOST PUMP TO STA 520R											
1301		20		HA		1-5	28-43-11	D00872		2		GD00172	DC..	E		YC051-YD152
1301		20		HA		1-8	28-43-11	D00872		2		GD00172	DC..	E		YD153-YD158, YL951-YN236, YN501-YR328
1302		20		VF	EP	30-4	28-43-11	D00872		3		D41852P		1		YC051-YC068
1302		20		VF	EP	29-0	28-43-11	D00872		3		D41852P		1		YC070-YD152
1302		20		VF	EP	29-2	28-43-11	D00872		3		D41852P		1		YD153-YD158, YL951-YN236, YN501-YR328
1302Z					EP	0-0	28-43-11	GD04402		ST..	E	GD00190	ST..	E		YC051-YD158, YL951-YN236, YN501-YR328
3601B		18		VH	A4	30-4	28-23-11	D05346P		2		D00074		3		YC051-YC068
3601B		18		VH	A4	29-0	28-23-11	D05346P		2		D00074		3		YC070-YD152
3601B		18		VH	A4	29-3	28-23-11	D05346P		2		D00074		3		YD153-YD158
3601B		16		VH	A4	29-3	28-23-11	D05346P		2		D00074		3		YL951-YN236, YN501-YR328
3601R		18		VH	A4	0-0	28-23-11	D05346P		4		D00074		1		YC051-YD158
3601R		16		VH	A4	0-0	28-23-11	D05346P		4		D00074		1		YL951-YN236, YN501-YR328
3601Y		18		VH	A4	0-0	28-23-11	D05346P		3		D00074		2		YC051-YD158
3601Y		16		VH	A4	0-0	28-23-11	D05346P		3		D00074		2		YL951-YN236, YN501-YR328
3601Z					A4	0-0	28-23-11	GD00190		ST..	E	GD04402	ST..	E		YC051-YD158, YL951-YN236, YN501-YR328
W1136		286A1136			NO.1 AFT BOOST PUMP TO STA 520L											
1303		20		HA		1-8	28-43-11	D00868		2		GD00184	DC..	E		ALL
1304		20		VF	ER	31-0	28-43-11	D00868		3		D41856P		1		YC051-YD152
1304		20		VF	ER	30-9	28-43-11	D00868		3		D41856P		1		YD153-YD158
1304		20		VF	ER	30-11	28-43-11	D00868		3		D41856P		1		YD160-YR328
1304Z					ER	0-0	28-43-11	GD04410		ST..	E	GD00947	ST..	E		ALL
3601B		18		VH	A4	31-3	28-23-11	D05342P		2		D00070		3		YC051-YD152
3601B		18		VH	A4	31-0	28-23-11	D05342P		2		D00070		3		YD153-YD158
3601B		16		VH	A4	31-2	28-23-11	D05342P		2		D00070		3		YD160-YR328
3601R		18		VH	A4	0-0	28-23-11	D05342P		4		D00070		1		YC051-YD158
3601R		16		VH	A4	0-0	28-23-11	D05342P		4		D00070		1		YD160-YR328
3601Y		18		VH	A4	0-0	28-23-11	D05342P		3		D00070		2		YC051-YD158

WIRE LIST

D280A108

91-21-11

Section W1130

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W1136	286A1136				NO.1 AFT BOOST PUMP TO STA 520L (continued)										
3601Y	16	VH	A4	0-0	28-23-11	D05342P	3				D00070	2			YD160-YR328
3601Z			A4	0-0	28-23-11	GD00947	ST..	E			GD04410	ST..	E		ALL
W1138	286A1138				RIGHT WING BODY PRESSURE SEAL TANK 2 FUEL QUANTITY										
001TI			AA	0-0	28-41-11	D39916				FA	D11314	= C1			YC051-YD158, YL951-YR328
001TO			AA	0-0	28-41-11	D39916		S/R			GD03952	ST..	E		YC051-YD158, YL951-YR328
001TX	20	C2	AA	20-2	28-41-11	D39916		17			D11314	1			YC051-YD158, YL951-YR328
1002	20	C1	AB	20-2	28-41-11	D39916		21			D11314	3			YC051-YD158, YL951-YR328
1002Z			AB	0-0	28-41-11	D39916		S/R			GD03952	ST..	E		YC051-YD158, YL951-YR328
1003	20	C1	AC	20-2	28-41-11	D39916		20			D11314	2			YC051-YD158, YL951-YR328
1003Z			AC	0-0	28-41-11	D39916		S/R			GD03952	ST..	E		YC051-YD158, YL951-YR328
1004	20	HA		0-7	28-41-11	D39916		38			D39916	39			YC051-YD158, YL951-YR328
1005	20	HA		0-7	28-41-11	D39916		7			D39916	6			YC051-YD158, YL951-YR328
1006	20	HA		0-7	28-41-11	D39916		16			D39916	S/R			YC051-YD158, YL951-YR328
FRAA				0-0	28-41-11	D39916		18			D39916			FA	YC051-YD158, YL951-YR328
FRAB				0-0	28-41-11	D39916		37			D39916			FA	YC051-YD158, YL951-YR328

WIRE LIST
D280A108

91-21-11
Section W1130
Page 2 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1140	286A1140			LEFT WING BODY PRESSURE SEAL TO TANK 1 FUEL QUANTITY											
001TI				AA	0-0	28-41-11	D39915			FA	D11312	= C1			YC051-YD158, YL951-YR328
001TO				AA	0-0	28-41-11	D39915	S/R			GD03950	ST..	E		YC051-YD158, YL951-YR328
001TX	20	C2		AA	20-2	28-41-11	D39915	17			D11312	1			YC051-YD158, YL951-YR328
1002	20	C1		AB	20-2	28-41-11	D39915	21			D11312	3			YC051-YD158, YL951-YR328
1002Z				AB	0-0	28-41-11	D39915	S/R			GD03950	ST..	E		YC051-YD158, YL951-YR328
1003	20	C1		AC	20-2	28-41-11	D39915	20			D11312	2			YC051-YD158, YL951-YR328
1003Z				AC	0-0	28-41-11	D39915	S/R			GD03950	ST..	E		YC051-YD158, YL951-YR328
1004	20	HA			0-7	28-41-11	D39915	38			D39915	39			YC051-YD158, YL951-YR328
1005	20	HA			0-7	28-41-11	D39915	7			D39915	6			YC051-YD158, YL951-YR328
1006	20	HA			0-7	28-41-11	D39915	16			D39915	S/R			YC051-YD158, YL951-YR328
FRAA					0-0	28-41-11	D39915	18			D39915			FA	YC051-YD158, YL951-YR328
FRAB					0-0	28-41-11	D39915	37			D39915			FA	YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W1140

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1162	286A1162			ENGINE STRUT-LEFT-FIREWALL TO AW0258L POWER FEEDER											
0001	*1		HA		8-9	24-21-11	D08094P		A		D30238		A		YC051-YC059
0001	*1		HA		10-0	24-21-11	D08094P		A		D30238		A		YC060-YR328
0002	*1		HA		8-9	24-21-11	D08094P		B		D30238		B		YC051-YC059
0002	*1		HA		10-0	24-21-11	D08094P		B		D30238		B		YC060-YR328
0003	*1		HA		8-9	24-21-11	D08094P		C		D30238		C		YC051-YC059
0003	*1		HA		10-0	24-21-11	D08094P		C		D30238		C		YC060-YR328
0004	04		HA		8-9	24-21-11	D08094P		D	HL	D30238		D	HD	YC051-YC059
0004	04		HA		10-0	24-21-11	D08094P		D	HL	D30238		D	HD	YC060-YR328
W1164	286A1164			ENGINE STRUT-LEFT FIREWALL TO AW0258L IDG CONTROLS											
0001	20		HL		2-0	80-11-11	D30234		39		GD03836	DC..	1		ALL
0002	20		HL		5-0	80-11-11	D30234		21		GD03828	ST..	1		YC051-YC054
0002	20		HL		2-0	80-11-11	D30234		21		GD03836	ST..	1		YC055-YR328
0003	20		HL		2-0	80-11-11	D30234		9		GD03836	DC..	1		ALL
0005	20		HL		2-0	29-11-11	D30234		19		GD03836	DC..	1		ALL
0006	20		HL		2-0	76-21-11	D30234		42		GD03836	DC..	1		ALL
0007	20		HL		2-0	76-21-11	D30234		23		GD03836	DC..	1		ALL
1003	20		HP	AA	11-0	80-11-11	D30016		18		D30234		38		YC051-YC054
1003	20		HP	AA	10-9	80-11-11	D30016		18		D30234		38		YC055-YR328
1003Z				AA	0-0	80-11-11	D30016		S/R		D30234		S/R		ALL
1005	20		HP	AB	11-0	80-11-11	D30016		38		D30234		22		YC051-YC054
1005	20		HP	AB	10-9	80-11-11	D30016		38		D30234		22		YC055-YR328
1005Z				AB	0-0	80-11-11	D30016		S/R		D30234		S/R		ALL
1006	20		HP	AE	11-0	76-21-11	D30016		39		D30234		40		YC051-YC054
1006	20		HP	AE	10-9	76-21-11	D30016		39		D30234		40		YC055-YR328
1006Z				AE	0-0	76-21-11	D30016		S/R		D30234		S/R		ALL
1009	20		HP	AJ	11-0	29-11-11	D30016		25		D30234		36		ALL
1009Z				AJ	0-0	29-11-11	D30016		S/R		D30234		S/R		ALL
1011	18		HP	AM	11-0	24-11-11	D30016		17		D30234		25		YC051-YC054
1011	18		HP	AM	10-9	24-11-11	D30016		17		D30234		25		YC055-YD158, YN231
1011	18		HP	AM	10-9	24-11-11	D30016		7		D30234		25		YD160-YL999, YN232-YR328
1011Z				AM	0-0	24-11-11	D30016		S/R		D30234		S/R		ALL
1012	18		HP	AU	2-0	24-11-11	D30234		11		GD03836	DC..	1		ALL
1012Z				AU	0-0	24-11-11	D30234		S/R		GD03836	DED			ALL
2001B	20		HQ	AD	11-0	77-12-21	D30016		29		D30234		5		YC051-YC054
2001B	20		HQ	AD	10-9	77-12-21	D30016		29		D30234		5		YC055-YR328
2001R	20		HQ	AD	0-0	77-12-21	D30016		30		D30234		15		YC051-YD158, YN231

WIRE LIST

D280A108

91-21-11

Section W1160

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity	
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W1164	286A1164			ENGINE STRUT-LEFT FIREWALL TO AW0258L IDG CONTROLS (continued)											
2001R	20		HQ	AD	0-0	77-12-21	D30016		21			D30234	15		YD160-YL999, YN232-YR328
2001Z				AD	0-0	77-12-21	D30016		S/R			D30234	S/R		ALL
2002B	20		HQ	AH	11-0	76-21-11	D30016		19			D30234	24		YC051-YC054
2002B	20		HQ	AH	10-9	76-21-11	D30016		19			D30234	24		YC055-YR328
2002R	20		HQ	AH	0-0	76-21-11	D30016		8			D30234	41		ALL
2002Z				AH	0-0	76-21-11	D30016		S/R			D30234	S/R		ALL
2003B	20		HQ	AL	11-0	24-11-11	D30016		2			D30234	31		YC051-YC054
2003B	20		HQ	AL	10-9	24-11-11	D30016		2			D30234	31		YC055-YD158, YN231
2003B	20		HQ	AL	10-9	24-11-11	D30016		9			D30234	31		YD160-YL999, YN232-YR328
2003R	20		HQ	AL	0-0	24-11-11	D30016		10			D30234	32		ALL
2003Z				AL	0-0	24-11-11	D30016		S/R			D30234	S/R		ALL
2004B	20		HQ	AP	11-0	24-21-11	D30016		4			D30234	33		YC051-YC054
2004B	20		HQ	AP	10-9	24-21-11	D30016		4			D30234	33		YC055-YD158, YN231
2004B	20		HQ	AP	10-9	24-21-11	D30016		24			D30234	33		YD160-YL999, YN232-YR328
2004R	20		HQ	AP	0-0	24-21-11	D30016		1			D30234	34		ALL
2004Z				AP	0-0	24-21-11	D30016		11	18		D30234	17		ALL
2005B	20		HQ	AS	11-0	SPARE	D30016		21			D30234	26		YC051-YC054
2005B	20		HQ	AS	10-9	SPARE	D30016		21			D30234	26		YC055-YD158, YN231
2005B	20		HQ	AS	10-9	SPARE	D30016		30			D30234	26		YD160-YL999, YN232-YR328
2005R	20		HQ	AS	0-0	SPARE	D30016		20			D30234	12		YC051-YD158, YN231
2005R	20		HQ	AS	0-0	SPARE	D30016		32			D30234	12		YD160-YL999, YN232-YR328
2005Z				AS	0-0	SPARE	D30016		S/R			D30234	S/R		ALL
2006B	20		HQ	AT	11-0	SPARE	D30016		37			D30234	37		YC051-YC054
2006B	20		HQ	AT	10-9	SPARE	D30016		37			D30234	37		YC055-YR328
2006R	20		HQ	AT	0-0	SPARE	D30016		36			D30234	20		ALL
2006Z				AT	0-0	SPARE	D30016		S/R			D30234	S/R		ALL
3001B	18		HR	AQ	11-0	24-21-11	D30016		14			D30234	8		YC051-YC054
3001B	18		HR	AQ	10-9	24-21-11	D30016		14			D30234	8		YC055-YR328
3001R	18		HR	AQ	0-0	24-21-11	D30016		12			D30234	3		ALL
3001Y	18		HR	AQ	0-0	24-21-11	D30016		5			D30234	6		YC051-YD158, YN231
3001Y	18		HR	AQ	0-0	24-21-11	D30016		16			D30234	6		YD160-YL999, YN232-YR328
3001Z				AQ	0-0	24-21-11	D30016		13	18		D30234	2		YC051-YD158, YN231

WIRE LIST

D280A108

91-21-11

Section W1160

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1164	286A1164				ENGINE STRUT-LEFT FIREWALL TO AW0258L IDG CONTROLS (continued)										
3001Z				AQ	0-0	24-21-11	D30016	23	18		D30234	2			YD160-YL999, YN232-YR328
4001B	20	HS	AR		11-0	24-24-11	D30016	33			D30234	28			YC051-YC054
4001B	20	HS	AR		10-9	24-24-11	D30016	33			D30234	28			YC055-YR328
4001G	20	HS	AR		0-0	24-24-11	D30016	15			D30234	29			YC051-YD158, YN231
4001G	20	HS	AR		0-0	24-24-11	D30016	22			D30234	29			YD160-YL999, YN232-YR328
4001R	20	HS	AR		0-0	24-24-11	D30016	31			D30234	13			YC051-YD158, YN231
4001R	20	HS	AR		0-0	24-24-11	D30016	34			D30234	13			YD160-YL999, YN232-YR328
4001Y	20	HS	AR		0-0	24-24-11	D30016	32			D30234	27			YC051-YD158, YN231
4001Y	20	HS	AR		0-0	24-24-11	D30016	20			D30234	27			YD160-YL999, YN232-YR328
4001Z				AR	0-0	24-24-11	D30016	S/R			D30234	S/R			ALL
W1166	286A1166				ENGINE STRUT-LEFT FIREWALL TO AW0258L EEC CH B										
0001	20	HL			1-7	74-11-11	D30256	1			GD03840	AC..	1		YC051-YC054
0001	20	HL			2-0	74-11-11	D30256	1			GD03840	AC..	1		YC055-YR328
0002	20	HL			1-7	73-22-11	D30256	7			GD03840	AC..	1		YC051-YC054
0002	20	HL			2-0	73-22-11	D30256	7			GD03840	AC..	1		YC055-YR328
0010	18	HL			3-0	26-12-11	GD03842	ST..	GW		GD03828	ST..	1		YC051-YC054
0010	18	HL			4-0	26-12-11	GD03842	ST..	GW		GD03840	ST..	1		YC055-YR328
1001	20	HP	AA		10-3	74-11-11	D30064	14			D30256	6			ALL
1001Z			AA		0-0	74-11-11	D30064	S/R			D30256	S/R			ALL
1003R	20	H9	AC		9-10	26-11-11	D30064	5			D30220	3			YC051-YC054
1003R	20	H9	AC		9-9	26-11-11	D30064	5			D30220	3			YC055-YR328
1003Z			AC		0-0	26-11-11	D30064	S/R			D30220	S/R			ALL
1004R	20	H9	AD		9-10	26-11-11	D30064	4			D30220	4			YC051-YC054
1004R	20	H9	AD		9-9	26-11-11	D30064	4			D30220	4			YC055-YR328
1004Z			AD		0-0	26-11-11	D30064	S/R			D30220	S/R			ALL
1005R	18	9L	AE		7-10	26-12-11	D30064	8	18		M01761	=B	GW		YC051-YC054
1005R	18	9L	AE		8-0	26-12-11	D30064	8	18		M01761	=B	GW		YC055-YR328
1005Z			AE		0-0	26-12-11	D30064	S/R			M01761			FA	ALL
1006R	18	9L	AF		7-10	26-12-11	D30064	6	18		M01761	=A	GW		YC051-YC054
1006R	18	9L	AF		8-0	26-12-11	D30064	6	18		M01761	=A	GW		YC055-YR328
1006Z			AF		0-0	26-12-11	D30064	S/R			M01761			FA	ALL
1008	20	HP	AH		10-3	73-22-11	D30064	21			D30256	2			ALL
1008Z			AH		0-0	73-22-11	D30064	S/R			D30256	S/R			ALL
2001B	20	HQ	AK		9-10	SPARE	D30064	16			D30220	2			YC051-YC054

WIRE LIST

D280A108

91-21-11

Section W1160

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	Wire No.	GA	CO TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W1166	286A1166			ENGINE STRUT-LEFT FIREWALL TO AW0258L EEC CH B (continued)												
2001B	20	HQ	AK		9-9	SPARE	D30064		16			D30220	2			YC055-YR328
2001R	20	HQ	AK		0-0	SPARE	D30064		15			D30220	1			ALL
2001Z			AK		0-0	SPARE	D30064		S/R			D30220	S/R			ALL
2002B	20	HQ	AL		10-3	SPARE	D30064		18			D30256	4			ALL
2002R	20	HQ	AL		0-0	SPARE	D30064		17			D30256	3			ALL
2002Z			AL		0-0	SPARE	D30064		S/R			D30256	S/R			ALL
FRAA					0-0	26-12-11	M01761			FA		GD03842	ST..	GW		ALL
W1168	286A1168			ENGINE STRUT-LEFT FIREWALL TO AW0258L EEC CH B												
0002	20	GK			0-7	73-21-11	D30260		36			D30260	19			YN231-YN501
0012	20	HL			0-7	73-21-11	D30260		36			D30260	20			YC056-YC058
0012	20	GK			0-7	73-21-11	D30260		36			D30260	20			YC059-YL999, YR301-YR328
1001	20	E4	AB		4-8	31-35-05	D30084		1			D00526	3			YL963-YL999, YN236-YR328
1001Z			AB		0-0	31-35-05	D30084		PERB			D00526	PERB			YL963-YL999, YN236-YR328
1014	20	HP	BB		10-9	36-11-11	D30084		3			D30204	3			YC056-YC058
1014	20	E4	BB		10-9	36-11-11	D30084		3			D30204	3			YC059-YR328
1014Z			BB		0-0	36-11-11	D30084		PERB			D30204	PERB			YC056-YR328
2003B	20	HQ	AE		12-2	78-35-11	D30260		14			D30208	7			YC056-YC058
2003B	20	E5	AE		12-2	78-35-11	D30260		14			D30208	7			YC059-YR328
2003R	20	HQ	AE		0-0	78-35-11	D30260		5			D30208	6			YC056-YC058
2003R	20	E5	AE		0-0	78-35-11	D30260		5			D30208	6			YC059-YR328
2003Z			AE		0-0	78-35-11	D30260		PERB			D30208	PERB			YC056-YR328
2004B	20	HQ	AG		3-5	78-35-11	D30260		21			D30210	7			YC056-YC058
2004B	20	E5	AG		3-5	78-35-11	D30260		21			D30210	7			YC059-YR328
2004R	20	HQ	AG		0-0	78-35-11	D30260		8			D30210	6			YC056-YC058
2004R	20	E5	AG		0-0	78-35-11	D30260		8			D30210	6			YC059-YR328
2004Z			AG		0-0	78-35-11	D30260		PERB			D30210	PERB			YC056-YR328
2007R	20	RJ	AN		10-9	77-31-11	D30084		8			D30204	6			YC056-YR328
2007W	20	RJ	AN		0-0	77-31-11	D30084		18			D30204	7			YC056-YR328
2007Z			AN		0-0	77-31-11	D30084		7			D30204	1			YC056-YR328
2008B	20	HQ	AA		8-6	73-21-11	D30084		23			D30260	10			YC056-YC058
2008B	20	E5	AA		8-6	73-21-11	D30084		23			D30260	10			YC059-YR328
2008R	20	HQ	AA		0-0	73-21-11	D30084		22			D30260	9			YC056-YC058
2008R	20	E5	AA		0-0	73-21-11	D30084		22			D30260	9			YC059-YR328
2008Z			AA		0-0	73-21-11	D30084		PERB			D30260	PERB			YC056-YR328
2009B	20	HQ	AR		8-6	73-21-21	D30084		11			D30260	27			YC056-YC058

WIRE LIST

D280A108

91-21-11

Section W1160

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1168	286A1168			ENGINE STRUT-LEFT FIREWALL TO AW0258L EEC CH B (continued)											
2009B	20	E5	AR		8-6	73-21-21	D30084	11			D30260	27			YC059-YR328
2009R	20	HQ	AR		0-0	73-21-21	D30084	26			D30260	13			YC056-YC058
2009R	20	E5	AR		0-0	73-21-21	D30084	26			D30260	13			YC059-YR328
2009Z			AR		0-0	73-21-21	D30084	PERB			D30260	PERB			YC056-YR328
2010B	20	HQ	AS		8-6	73-21-21	D30084	27			D30260	26			YC056-YC058
2010B	20	E5	AS		8-6	73-21-21	D30084	27			D30260	26			YC059-YR328
2010R	20	HQ	AS		0-0	73-21-21	D30084	28			D30260	12			YC056-YC058
2010R	20	E5	AS		0-0	73-21-21	D30084	28			D30260	12			YC059-YR328
2010Z			AS		0-0	73-21-21	D30084	PERB			D30260	PERB			YC056-YR328
2011B	20	HQ	AT		8-6	73-21-21	D30084	25			D30260	25			YC056-YC058
2011B	20	E5	AT		8-6	73-21-21	D30084	25			D30260	25			YC059-YR328
2011R	20	HQ	AT		0-0	73-21-21	D30084	24			D30260	11			YC056-YC058
2011R	20	E5	AT		0-0	73-21-21	D30084	24			D30260	11			YC059-YR328
2011Z			AT		0-0	73-21-21	D30084	PERB			D30260	PERB			YC056-YR328
2012B	20	HQ	AU		8-6	73-24-11	D30084	34			D30260	4			YC056-YC058
2012B	20	E5	AU		8-6	73-24-11	D30084	34			D30260	4			YC059-YR328
2012R	20	HQ	AU		0-0	73-24-11	D30084	15			D30260	1			YC056-YC058
2012R	20	E5	AU		0-0	73-24-11	D30084	15			D30260	1			YC059-YR328
2012Z			AU		0-0	73-24-11	D30084	PERB			D30260	PERB			YC056-YR328
2013B	20	HQ	AV		8-6	73-24-12	D30084	35			D30260	3			YC056-YC058
2013B	20	E5	AV		8-6	73-24-12	D30084	35			D30260	3			YC059-YR328
2013R	20	HQ	AV		0-0	73-24-12	D30084	36			D30260	2			YC056-YC058
2013R	20	E5	AV		0-0	73-24-12	D30084	36			D30260	2			YC059-YR328
2013Z			AV		0-0	73-24-12	D30084	PERB			D30260	PERB			YC056-YR328
2015B	20	HQ	BH		10-9	SPARE	D30084	14			D30204	13			YC056-YC058
2015B	20	E5	BH		10-9	SPARE	D30084	14			D30204	13			YC059-YR328
2015R	20	HQ	BH		0-0	SPARE	D30084	5			D30204	4			YC056-YC058
2015R	20	E5	BH		0-0	SPARE	D30084	5			D30204	4			YC059-YR328
2015Z			BH		0-0	SPARE	D30084	PERB			D30204	PERB			YC056-YR328
2016B	20	HQ	BJ		8-6	SPARE	D30084	31			D30260	39			YC056-YC058
2016B	20	E5	BJ		8-6	SPARE	D30084	31			D30260	39			YC059-YR328
2016R	20	HQ	BJ		0-0	SPARE	D30084	30			D30260	22			YC056-YC058
2016R	20	E5	BJ		0-0	SPARE	D30084	30			D30260	22			YC059-YR328
2016Z			BJ		0-0	SPARE	D30084	PERB			D30260	PERB			YC056-YR328
2018B	20	HQ	AZ		10-9	36-11-11	D30084	2			D30204	11			YC056-YC058
2018B	20	E5	AZ		10-9	36-11-11	D30084	2			D30204	11			YC059-YR328
2018R	20	HQ	AZ		0-0	36-11-11	D30084	10			D30204	12			YC056-YC058
2018R	20	E5	AZ		0-0	36-11-11	D30084	10			D30204	12			YC059-YR328
2018Z			AZ		0-0	36-11-11	D30084	PERB			D30204	PERB			YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W1160

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W1168	286A1168				ENGINE STRUT-LEFT FIREWALL TO AW0258L EEC CH B (continued)											
2019B	20	HQ	BC		9-1	36-11-11	D30204		2			SM00002		V1		YC056-YC058
2019B	20	E5	BC		9-8	36-11-11	D30204		2			SM00002		V1		YC059-YL959, YN231-YN235
2019B	20	E5	BC		9-7	36-11-11	D30204		2			SM00002		V1		YL963-YL999, YN236-YR328
2019R	20	HQ	BC		0-0	36-11-11	D30204		10			SM00001		V1		YC056-YC058
2019R	20	E5	BC		0-0	36-11-11	D30204		10			SM00001		V1		YC059-YR328
2019Z			BC		0-0	36-11-11	D30204	PERB				SM00001	REF		AA	YC056-YR328
2020B	20	HQ	BE		3-0	36-11-11	D00526		1			SM00002		V1		YC056-YC058
2020B	20	E5	BE		3-7	36-11-11	D00526		1			SM00002		V1		YC059-YL959, YN231-YN235
2020B	20	E5	BE		3-6	36-11-11	D00526		1			SM00002		V1		YL963-YL999, YN236-YR328
2020R	20	HQ	BE		0-0	36-11-11	D00526		2			SM00001		V1		YC056-YC058
2020R	20	E5	BE		0-0	36-11-11	D00526		2			SM00001		V1		YC059-YR328
2020Z			BE		0-0	36-11-11	D00526	PERB				SM00001	REF		AA	YC056-YR328
2021B	20	HQ	BD		2-3	36-11-11	D30084		29			SM00002		V1		YC056-YC058
2021B	20	E5	BD		1-8	36-11-11	D30084		29			SM00002		V1		YC059-YL959, YN231-YN235
2021B	20	E5	BD		1-9	36-11-11	D30084		29			SM00002		V1		YL963-YL999, YN236-YR328
2021R	20	HQ	BD		0-0	36-11-11	D30084		12			SM00001		V1		YC056-YC058
2021R	20	E5	BD		0-0	36-11-11	D30084		12			SM00001		V1		YC059-YR328
2021Z			BD		0-0	36-11-11	D30084	PERB				SM00001	REF		AA	YC056-YR328
2022B	20	HQ	AC		8-6	78-35-11	D30084		13			D30260	32			YC056-YC058
2022B	20	E5	AC		8-6	78-35-11	D30084		13			D30260	32			YC059-YR328
2022R	20	HQ	AC		0-0	78-35-11	D30084		4			D30260	33			YC056-YC058
2022R	20	E5	AC		0-0	78-35-11	D30084		4			D30260	33			YC059-YR328
2022Z			AC		0-0	78-35-11	D30084	PERB				D30260	PERB			YC056-YR328
2023B	20	HQ	AP		8-6	73-21-12	D30084		9			D30260	42			YC056-YC058
2023B	20	E5	AP		8-6	73-21-12	D30084		9			D30260	42			YC059-YR328
2023R	20	HQ	AP		0-0	73-21-12	D30084		21			D30260	24			YC056-YC058
2023R	20	E5	AP		0-0	73-21-12	D30084		21			D30260	24			YC059-YR328
2023Z			AP		0-0	73-21-12	D30084	PERB				D30260	PERB			YC056-YR328
2024B	20	HQ	AX		10-9	30-11-11	D30084		16			D30204	5			YC056-YC058
2024B	20	E5	AX		10-9	30-11-11	D30084		16			D30204	5			YC059-YR328
2024R	20	HQ	AX		0-0	30-11-11	D30084		6			D30204	14			YC056-YC058
2024R	20	E5	AX		0-0	30-11-11	D30084		6			D30204	14			YC059-YR328
2024Z			AX		0-0	30-11-11	D30084	PERB				D30204	PERB			YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W1160

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1168	286A1168			ENGINE STRUT-LEFT FIREWALL TO AW0258L EEC CH B (continued)											
2030B	20	E5	BA		4-8	31-35-05	D30084	32			D00526	5			YL963-YL999, YN236-YR328
2030R	20	E5	BA		0-0	31-35-05	D30084	33			D00526	4			YL963-YL999, YN236-YR328
2030Z			BA		0-0	31-35-05	D30084	PERB			D00526	PERB			YL963-YL999, YN236-YR328
3001B	20	HR	AF		12-2	78-35-11	D30260	18			D30208	2			YC056-YC058
3001B	20	E6	AF		12-2	78-35-11	D30260	18			D30208	2			YC059-YR328
3001R	20	HR	AF		0-0	78-35-11	D30260	17			D30208	3			YC056-YC058
3001R	20	E6	AF		0-0	78-35-11	D30260	17			D30208	3			YC059-YR328
3001Y	20	HR	AF		0-0	78-35-11	D30260	34			D30208	10			YC056-YC058
3001Y	20	E6	AF		0-0	78-35-11	D30260	34			D30208	10			YC059-YR328
3001Z			AF		0-0	78-35-11	D30260	PERB			D30208	PERB			YC056-YR328
3002B	20	HR	AH		3-5	78-35-11	D30260	41			D30210	2			YC056-YC058
3002B	20	E6	AH		3-5	78-35-11	D30260	41			D30210	2			YC059-YR328
3002R	20	HR	AH		0-0	78-35-11	D30260	23			D30210	3			YC056-YC058
3002R	20	E6	AH		0-0	78-35-11	D30260	23			D30210	3			YC059-YR328
3002Y	20	HR	AH		0-0	78-35-11	D30260	40			D30210	10			YC056-YC058
3002Y	20	E6	AH		0-0	78-35-11	D30260	40			D30210	10			YC059-YR328
3002Z			AH		0-0	78-35-11	D30260	PERB			D30210	PERB			YC056-YR328
3003B	20	HR	AL		7-3	78-36-11	D30210	5			D30084	19			YC056-YC058
3003B	20	E6	AL		7-3	78-36-11	D30210	5			D30084	19			YC059-YR328
3003R	20	HR	AL		0-0	78-36-11	D30210	4			D30084	20			YC056-YC058
3003R	20	E6	AL		0-0	78-36-11	D30210	4			D30084	20			YC059-YR328
3003Y	20	HR	AL		0-0	78-36-11	D30210	1			D30084	39			YC056-YC058
3003Y	20	E6	AL		0-0	78-36-11	D30210	1			D30084	39			YC059-YR328
3003Z			AL		0-0	78-36-11	D30210	PERB			D30084	PERB			YC056-YR328
3004B	20	HR	AM		9-0	78-36-11	D30208	5			D30084	38			YC056-YC058
3004B	20	E6	AM		9-0	78-36-11	D30208	5			D30084	38			YC059-YR328
3004R	20	HR	AM		0-0	78-36-11	D30208	4			D30084	37			YC056-YC058
3004R	20	E6	AM		0-0	78-36-11	D30208	4			D30084	37			YC059-YR328
3004Y	20	HR	AM		0-0	78-36-11	D30208	1			D30084	17			YC056-YC058
3004Y	20	E6	AM		0-0	78-36-11	D30208	1			D30084	17			YC059-YR328
3004Z			AM		0-0	78-36-11	D30208	PERB			D30084	PERB			YC056-YR328
YAAA					0-0	78-35-11	D30084	PERB			OAS0001				YC056-YL999, YR301-YR328
YAAA					0-0	78-35-11	D30084	PERB			OAS0001	PERB			YN231-YN501
YAAB					0-0	36-11-11	D00526	PERB			OAS0004	PERB			YC056-YR328
YAAC					0-0	78-35-11	D30208	PERB			OAS0004	PERB			YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W1160

Page 7

Nov 12/2012



Bundle No.	Part Number	Description	From	To
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice Effectivity

W1168 286A1168 ENGINE STRUT-LEFT FIREWALL TO AW0258L EEC CH B (continued)

YAAD	0-0	78-36-11	D30210	PERB	OAS0002	PERB	YC056-YR328
YAAE	0-0	36-11-11	D30204	PERB	OAS0003	PERB	YC056-YR328
YAAF	0-0	73-21-21	D30260	PERB	OAS0003	PERB	YC056-YR328
YAAG	0-0	78-36-11	OAS0002	PERB	OAS0003	PERB	YC056-YR328
YAAH	0-0	78-35-11	OAS0001	PERB	OAS0002	PERB	YC056-YR328
YAAJ	0-0	78-35-11	OAS0001	PERB	OAS0004	PERB	YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W1160

Page 8 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From			To			Effectivity		
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W1170	286A1170			ENGINE STRUT LEFT FIREWALL TO AW0258L EEC CH A											
0002	20		HL		2-0	30-21-11	D30228		4		GD03838	DC..	1		ALL
0009	18		HL		2-0	30-21-11	D30228		11		GD03838	DC..	1		ALL
0010	18		HL		2-0	30-21-11	D30228		13		GD03838	DC..	1		ALL
0012	18		HL		2-0	30-21-11	D30228		26		GD03838	DC..	1		ALL
0015	18		HL		2-0	30-21-11	D30228		28		GD03838	DC..	1		ALL
1001	20		HP	AB	9-7	74-11-11	D08056P		22		D30212		6		ALL
1001Z				AB	0-0	74-11-11	D08056P		S/R		D30212		S/R		ALL
1002	20		HP	AC	3-0	74-11-11	D30212		7		GD03840	AC..	1		ALL
1002Z				AC	0-0	74-11-11	D30212		S/R		GD03840	ST..	1		ALL
1003R	20		H9	AD	10-0	26-11-11	D08056P		19		D30252		2		ALL
1003Z				AD	0-0	26-11-11	D08056P		S/R		D30252		S/R		ALL
1004R	20		H9	AE	10-0	26-11-11	D08056P		20		D30252		1		ALL
1004Z				AE	0-0	26-11-11	D08056P		S/R		D30252		S/R		ALL
1005	20		HP	AG	9-7	73-22-11	D08056P		23		D30212		4		ALL
1005Z				AG	0-0	73-22-11	D08056P		S/R		D30212		S/R		ALL
1006	20		HP	AH	3-0	73-22-11	D30212		5		GD03840	AC..	1		ALL
1006Z				AH	0-0	73-22-11	D30212		S/R		GD03840	ST..	1		ALL
1007	20		HP	AK	10-11	30-21-11	D08056P		18		D30228		1		ALL
1007Z				AK	0-0	30-21-11	D08056P		S/R		D30228		S/R		ALL
1013	20		HP	AR	1-9	30-21-11	D30228		12		SM00001		V1		ALL
1013Z				AR	0-0	30-21-11	D30228		S/R		SM00001	REF		AA	ALL
1014	20		HP	AS	1-9	30-21-11	D30228		27		SM00001		V1		ALL
1014Z				AS	0-0	30-21-11	D30228		S/R		SM00001	REF		AA	ALL
1016	20		HP	AU	9-8	30-21-11	D08056P		21		SM00001		V1		ALL
1016Z				AU	0-0	30-21-11	D08056P		S/R		SM00001	REF		AA	ALL
1017	20		HP	AZ	10-11	31-62-14	D08056P		11		D30228		25		ALL
1017Z				AZ	0-0	31-62-14	D08056P		S/R		D30228		S/R		ALL
1018	20		HP	BA	10-11	31-62-14	D30228		29		D08056P		24		ALL
1018Z				BA	0-0	31-62-14	D30228		S/R		D08056P		S/R		ALL
2001R	20		RJ	AA	10-11	77-31-11	D08056P		17		D30228		18		ALL
2001W	20		RJ	AA	0-0	77-31-11	D08056P		6		D30228		19		ALL
2001Z				AA	0-0	77-31-11	D08056P		7	18	D30228		7		ALL
2002B	20		HQ	AJ	9-7	77-12-11	D08056P		16		D30212		9		ALL
2002R	20		HQ	AJ	0-0	77-12-11	D08056P		15		D30212		8		ALL
2002Z				AJ	0-0	77-12-11	D08056P		S/R		D30212		S/R		ALL
2003B	20		HQ	AV	10-11	30-21-11	D08056P		9		D30228		24		ALL
2003R	20		HQ	AV	0-0	30-21-11	D08056P		8		D30228		14		ALL
2003Z				AV	0-0	30-21-11	D08056P		S/R		D30228		S/R		ALL
2004B	20		HQ	AW	10-0	SPARE	D08056P		13		D30252		4		ALL

WIRE LIST

D280A108

91-21-11

Section W1170

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1170	286A1170			ENGINE STRUT LEFT FIREWALL TO AW0258L EEC CH A (continued)											
2004R	20	HQ	AW	0-0	SPARE	D08056P		12			D30252	3			ALL
2004Z			AW	0-0	SPARE	D08056P		S/R			D30252	S/R			ALL
2005B	20	HQ	AX	9-7	SPARE	D08056P		14			D30212	2			ALL
2005R	20	HQ	AX	0-0	SPARE	D08056P		4			D30212	1			ALL
2005Z			AX	0-0	SPARE	D08056P		S/R			D30212	S/R			ALL
2006B	20	HQ	AY	10-11	SPARE	D08056P		10			D30228	16			ALL
2006R	20	HQ	AY	0-0	SPARE	D08056P		2			D30228	15			ALL
2006Z			AY	0-0	SPARE	D08056P		S/R			D30228	S/R			ALL
3001B	20	HR	AF	10-11	79-31-11	D08056P		5			D30228	20			ALL
3001R	20	HR	AF	0-0	79-31-11	D08056P		1			D30228	8			ALL
3001Y	20	HR	AF	0-0	79-31-11	D08056P		3			D30228	21			ALL
3001Z			AF	0-0	79-31-11	D08056P		S/R			D30228	S/R			ALL
W1172	286A1172			ENGINE STRUT-LEFT FIREWALL TO AW0258L EEC CH A											
0003	20	HL		0-7	73-21-11	D30224		27			D30224	28			YC056-YC058
0003	20	GK		0-7	73-21-11	D30224		27			D30224	28			YC059-YR328
2003B	20	HQ	AE	12-5	78-35-11	D30224		41			D30202	9			YC056-YC058
2003B	20	E5	AE	12-5	78-35-11	D30224		41			D30202	9			YC059-YR328
2003R	20	HQ	AE	0-0	78-35-11	D30224		40			D30202	10			YC056-YC058
2003R	20	E5	AE	0-0	78-35-11	D30224		40			D30202	10			YC059-YR328
2003Z			AE	0-0	78-35-11	D30224		PERB			D30202	PERB			YC056-YR328
2004B	20	HQ	AG	4-4	78-35-11	D30224		38			D30206	9			YC056-YC058
2004B	20	E5	AG	4-4	78-35-11	D30224		38			D30206	9			YC059-YR328
2004R	20	HQ	AG	0-0	78-35-11	D30224		39			D30206	10			YC056-YC058
2004R	20	E5	AG	0-0	78-35-11	D30224		39			D30206	10			YC059-YR328
2004Z			AG	0-0	78-35-11	D30224		PERB			D30206	PERB			YC056-YR328
2007B	20	HQ	AN	9-8	73-21-11	D30042		23			D30224	3			YC056-YC058
2007B	20	E5	AN	9-5	73-21-11	D30042		23			D30224	3			YC059-YR328
2007R	20	HQ	AN	0-0	73-21-11	D30042		22			D30224	2			YC056-YC058
2007R	20	E5	AN	0-0	73-21-11	D30042		22			D30224	2			YC059-YR328
2007Z			AN	0-0	73-21-11	D30042		PERB			D30224	PERB			YC056-YR328
2008B	20	HQ	AS	9-8	73-21-12	D30042		31			D30224	37			YC056-YC058
2008B	20	E5	AS	9-5	73-21-12	D30042		31			D30224	37			YC059-YR328
2008R	20	HQ	AS	0-0	73-21-12	D30042		30			D30224	20			YC056-YC058
2008R	20	E5	AS	0-0	73-21-12	D30042		30			D30224	20			YC059-YR328
2008Z			AS	0-0	73-21-12	D30042		PERB			D30224	PERB			YC056-YR328
2009B	20	HQ	AT	9-8	73-21-21	D30042		11			D30224	33			YC056-YC058
2009B	20	E5	AT	9-5	73-21-21	D30042		11			D30224	33			YC059-YR328
2009R	20	HQ	AT	0-0	73-21-21	D30042		26			D30224	17			YC056-YC058

WIRE LIST

D280A108

91-21-11

Section W1170

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1172	286A1172			ENGINE STRUT-LEFT FIREWALL TO AW0258L EEC CH A (continued)											
2009R	20	E5	AT		0-0	73-21-21	D30042	26			D30224	17			YC059-YR328
2009Z			AT		0-0	73-21-21	D30042	PERB			D30224	PERB			YC056-YR328
2010B	20	HQ	AU		9-8	73-21-21	D30042	27			D30224	34			YC056-YC058
2010B	20	E5	AU		9-5	73-21-21	D30042	27			D30224	34			YC059-YR328
2010R	20	HQ	AU		0-0	73-21-21	D30042	28			D30224	18			YC056-YC058
2010R	20	E5	AU		0-0	73-21-21	D30042	28			D30224	18			YC059-YR328
2010Z			AU		0-0	73-21-21	D30042	PERB			D30224	PERB			YC056-YR328
2011B	20	HQ	AV		9-8	73-21-21	D30042	25			D30224	7			YC056-YC058
2011B	20	E5	AV		9-5	73-21-21	D30042	25			D30224	7			YC059-YR328
2011R	20	HQ	AV		0-0	73-21-21	D30042	24			D30224	6			YC056-YC058
2011R	20	E5	AV		0-0	73-21-21	D30042	24			D30224	6			YC059-YR328
2011Z			AV		0-0	73-21-21	D30042	PERB			D30224	PERB			YC056-YR328
2012B	20	HQ	AW		9-8	73-24-11	D30042	34			D30224	4			YC056-YC058
2012B	20	E5	AW		9-5	73-24-11	D30042	34			D30224	4			YC059-YR328
2012R	20	HQ	AW		0-0	73-24-11	D30042	33			D30224	1			YC056-YC058
2012R	20	E5	AW		0-0	73-24-11	D30042	33			D30224	1			YC059-YR328
2012Z			AW		0-0	73-24-11	D30042	PERB			D30224	PERB			YC056-YR328
2013B	20	HQ	AX		9-8	73-24-12	D30042	35			D30224	14			YC056-YC058
2013B	20	E5	AX		9-5	73-24-12	D30042	35			D30224	14			YC059-YR328
2013R	20	HQ	AX		0-0	73-24-12	D30042	15			D30224	5			YC056-YC058
2013R	20	E5	AX		0-0	73-24-12	D30042	15			D30224	5			YC059-YR328
2013Z			AX		0-0	73-24-12	D30042	PERB			D30224	PERB			YC056-YR328
2014B	20	HQ	AY		9-6	SPARE	D30042	12			D30202	11			YC056-YC058
2014B	20	E5	AY		9-3	SPARE	D30042	12			D30202	11			YC059-YR328
2014R	20	HQ	AY		0-0	SPARE	D30042	3			D30202	2			YC056-YC058
2014R	20	E5	AY		0-0	SPARE	D30042	3			D30202	2			YC059-YR328
2014Z			AY		0-0	SPARE	D30042	PERB			D30202	PERB			YC056-YR328
2016B	20	HQ	BA		7-10	SPARE	D30042	14			D30206	11			YC056-YC058
2016B	20	E5	BA		7-8	SPARE	D30042	14			D30206	11			YC059-YR328
2016R	20	HQ	BA		0-0	SPARE	D30042	32			D30206	2			YC056-YC058
2016R	20	E5	BA		0-0	SPARE	D30042	32			D30206	2			YC059-YR328
2016Z			BA		0-0	SPARE	D30042	PERB			D30206	PERB			YC056-YR328
2017B	20	HQ	BD		9-8	74-31-11	D30224	23			D30042	29			YC056-YC058
2017B	20	E5	BD		9-5	74-31-11	D30224	23			D30042	29			YC059-YR328
2017R	20	HQ	BD		0-0	74-31-11	D30224	22			D30042	13			YC056-YC058
2017R	20	E5	BD		0-0	74-31-11	D30224	22			D30042	13			YC059-YR328
2017Z			BD		0-0	74-31-11	D30224	PERB			D30042	PERB			YC056-YR328
2022B	20	HQ	AC		9-8	78-35-11	D30224	10			D30042	36			YC056-YC058
2022B	20	E5	AC		9-5	78-35-11	D30224	10			D30042	36			YC059-YR328

WIRE LIST

D280A108

91-21-11

Section W1170

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1172		286A1172			ENGINE STRUT-LEFT FIREWALL TO AW0258L EEC CH A (continued)											
2022R		20		HQ	AC	0-0	78-35-11	D30224			9	D30042		37		YC056-YC058
2022R		20		E5	AC	0-0	78-35-11	D30224			9	D30042		37		YC059-YR328
2022Z					AC	0-0	78-35-11	D30224		PERB		D30042		PERB		YC056-YR328
2023B		20		HQ	AQ	9-8	73-21-12	D30224			30	D30042		9		YC056-YC058
2023B		20		E5	AQ	9-5	73-21-12	D30224			30	D30042		9		YC059-YR328
2023R		20		HQ	AQ	0-0	73-21-12	D30224			15	D30042		21		YC056-YC058
2023R		20		E5	AQ	0-0	73-21-12	D30224			15	D30042		21		YC059-YR328
2023Z					AQ	0-0	73-21-12	D30224		PERB		D30042		PERB		YC056-YR328
3001B		20		HR	AF	12-5	78-35-11	D30224			35	D30202		5		YC056-YC058
3001B		20		E6	AF	12-5	78-35-11	D30224			35	D30202		5		YC059-YR328
3001R		20		HR	AF	0-0	78-35-11	D30224			19	D30202		6		YC056-YC058
3001R		20		E6	AF	0-0	78-35-11	D30224			19	D30202		6		YC059-YR328
3001Y		20		HR	AF	0-0	78-35-11	D30224			36	D30202		4		YC056-YC058
3001Y		20		E6	AF	0-0	78-35-11	D30224			36	D30202		4		YC059-YR328
3001Z					AF	0-0	78-35-11	D30224		PERB		D30202		PERB		YC056-YR328
3002B		20		HR	AH	4-4	78-35-11	D30224			16	D30206		5		YC056-YC058
3002B		20		E6	AH	4-4	78-35-11	D30224			16	D30206		5		YC059-YR328
3002R		20		HR	AH	0-0	78-35-11	D30224			31	D30206		6		YC056-YC058
3002R		20		E6	AH	0-0	78-35-11	D30224			31	D30206		6		YC059-YR328
3002Y		20		HR	AH	0-0	78-35-11	D30224			32	D30206		4		YC056-YC058
3002Y		20		E6	AH	0-0	78-35-11	D30224			32	D30206		4		YC059-YR328
3002Z					AH	0-0	78-35-11	D30224		PERB		D30206		PERB		YC056-YR328
3003B		18		HR	AB	9-6	78-32-51	D30202			12	D30042		7		YC056-YC058
3003B		18		E6	AB	9-3	78-32-51	D30202			12	D30042		7		YC059-YR328
3003R		18		HR	AB	0-0	78-32-51	D30202			3	D30042		17		YC056-YC058
3003R		18		E6	AB	0-0	78-32-51	D30202			3	D30042		17		YC059-YR328
3003Y		18		HR	AB	0-0	78-32-51	D30202			13	D30042		1		YC056-YC058
3003Y		18		E6	AB	0-0	78-32-51	D30202			13	D30042		1		YC059-YR328
3003Z					AB	0-0	78-32-51	D30202		PERB		D30042		PERB		YC056-YR328
3004B		18		HR	AA	7-10	78-32-51	D30206			12	D30042		16		YC056-YC058
3004B		18		E6	AA	7-8	78-32-51	D30206			12	D30042		16		YC059-YR328
3004R		18		HR	AA	0-0	78-32-51	D30206			3	D30042		6		YC056-YC058
3004R		18		E6	AA	0-0	78-32-51	D30206			3	D30042		6		YC059-YR328
3004Y		18		HR	AA	0-0	78-32-51	D30206			13	D30042		5		YC056-YC058
3004Y		18		E6	AA	0-0	78-32-51	D30206			13	D30042		5		YC059-YR328
3004Z					AA	0-0	78-32-51	D30206		PERB		D30042		PERB		YC056-YR328
3005B		20		HR	AL	7-10	78-36-11	D30206			8	D30042		19		YC056-YC058
3005B		20		E6	AL	7-8	78-36-11	D30206			8	D30042		19		YC059-YR328
3005R		20		HR	AL	0-0	78-36-11	D30206			7	D30042		20		YC056-YC058

WIRE LIST

D280A108

91-21-11

Section W1170

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1172	286A1172				ENGINE STRUT-LEFT FIREWALL TO AW0258L EEC CH A (continued)											
3005R	20	E6	AL		0-0	78-36-11		D30206		7		D30042	20			YC059-YR328
3005Y	20	HR	AL		0-0	78-36-11		D30206		1		D30042	8			YC056-YC058
3005Y	20	E6	AL		0-0	78-36-11		D30206		1		D30042	8			YC059-YR328
3005Z			AL		0-0	78-36-11		D30206		PERB		D30042	PERB			YC056-YR328
3006B	20	HR	AM		9-6	78-36-11		D30202		8		D30042	38			YC056-YC058
3006B	20	E6	AM		9-3	78-36-11		D30202		8		D30042	38			YC059-YR328
3006R	20	HR	AM		0-0	78-36-11		D30202		7		D30042	39			YC056-YC058
3006R	20	E6	AM		0-0	78-36-11		D30202		7		D30042	39			YC059-YR328
3006Y	20	HR	AM		0-0	78-36-11		D30202		1		D30042	18			YC056-YC058
3006Y	20	E6	AM		0-0	78-36-11		D30202		1		D30042	18			YC059-YR328
3006Z			AM		0-0	78-36-11		D30202		PERB		D30042	PERB			YC056-YR328
YAAA					0-0	78-35-21		D30224		PERB		OAS0001	PERB			YC056-YC058
YAAA					0-0	78-35-11		D30224		PERB		OAS0001	PERB			YC059-YR328
YAAB					0-0	78-35-21		D30206		PERB		OAS0001	PERB			YC056-YC058
YAAB					0-0	78-35-11		D30206		PERB		OAS0001	PERB			YC059-YR328
YAAC					0-0	73-21-21		D30042		PERB		OAS0002	PERB			YC056-YR328
YAAD					0-0	78-36-11		D30202		PERB		OAS0002	PERB			YC056-YR328
YAAE					0-0	78-32-51		OAS0001		PERB		OAS0002	PERB			YC056-YR328
W1178	286A1178				LEADING EDGE-LEFT WING EEC CH A											
1001	20	HW	AA		14-6	73-22-11		D39927		5		D08056J	23			YC051-YR319
1001	20	HW	AA		14-7	73-22-11		D39927		5		D08056J	23			YR320-YR328
1001Z			AA		0-0	73-22-11		D39927		S/R		D08056J	S/R			ALL
1002	20	HW	AB		14-6	74-11-11		D39927		3		D08056J	22			YC051-YR319
1002	20	HW	AB		14-7	74-11-11		D39927		3		D08056J	22			YR320-YR328
1002Z			AB		0-0	74-11-11		D39927		S/R		D08056J	S/R			ALL
1003	20	HP	AC		14-6	30-21-11		D39927		38		D08056J	18			YC051-YR319
1003	20	HP	AC		14-7	30-21-11		D39927		38		D08056J	18			YR320-YR328
1003Z			AC		0-0	30-21-11		D39927		S/R		D08056J	S/R			ALL
1004	20	HP	AD		14-6	30-21-11		D39927		21		D08056J	8			YC051-YR319
1004	20	HP	AD		14-7	30-21-11		D39927		21		D08056J	8			YR320-YR328
1004Z			AD		0-0	30-21-11		D39927		S/R		D08056J	S/R			ALL
1005	20	HP	AE		14-6	30-21-11		D39927		22		D08056J	9			YC051-YR319
1005	20	HP	AE		14-7	30-21-11		D39927		22		D08056J	9			YR320-YR328
1005Z			AE		0-0	30-21-11		D39927		S/R		D08056J	S/R			ALL
1006	20	HP	AF		14-6	30-21-11		D39927		23		D08056J	21			YC051-YR319
1006	20	HP	AF		14-7	30-21-11		D39927		23		D08056J	21			YR320-YR328
1006Z			AF		0-0	30-21-11		D39927		S/R		D08056J	S/R			ALL
1007R	20	H9	AG		14-6	26-11-11		D39927		28		D08056J	19			YC051-YR319

WIRE LIST

D280A108

91-21-11

Section W1170

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1178	286A1178			LEADING EDGE-LEFT WING EEC CH A (continued)											
1007R	20	H9	AG		14-7	26-11-11	D39927		28		D08056J	19			YR320-YR328
1007Z			AG		0-0	26-11-11	D39927		S/R		D08056J	S/R			ALL
1008R	20	H9	AH		14-6	26-11-11	D39927		29		D08056J	20			YC051-YR319
1008R	20	H9	AH		14-7	26-11-11	D39927		29		D08056J	20			YR320-YR328
1008Z			AH		0-0	26-11-11	D39927		S/R		D08056J	S/R			ALL
1009	20	HP	AQ		20-4	28-21-11	D00788		2		D39927	30			ALL
1009Z			AQ		0-0	28-21-11	D00788		S/R		D39927	S/R			ALL
1010	20	HP	AR		20-4	28-21-11	D00788		3		D39927	32			ALL
1010Z			AR		0-0	28-21-11	D00788		S/R		D39927	S/R			ALL
1011	18	HE	AS		1-9	28-21-11	D00788		4		GD03980	DC..	E	*	ALL
1011Z			AS		0-0	28-21-11	D00788		S/R		GD03980	DC..	E	*	ALL
1012	20	HP	AT		20-4	28-21-11	D00788		5		D39927	31			ALL
1012Z			AT		0-0	28-21-11	D00788		S/R		D39927	S/R			ALL
1013	18	HP	AU		1-10	28-21-11	D00788		7		GD03982	ST..	E	*	ALL
1013Z			AU		0-0	28-21-11	D00788		S/R		GD03982	ST..	E	*	ALL
1014	20	HP	AV		14-6	31-62-14	D39927		8		D08056J	11			YC051-YR319
1014	20	HP	AV		14-7	31-62-14	D39927		8		D08056J	11			YR320-YR328
1014Z			AV		0-0	31-62-14	D39927		S/R		D08056J	S/R			ALL
1015	20	HP	BA		14-6	31-62-14	D08056J		24		D39927	33			YC051-YR319
1015	20	HP	BA		14-7	31-62-14	D08056J		24		D39927	33			YR320-YR328
1015Z			BA		0-0	31-62-14	D08056J		S/R		D39927	S/R			ALL
2001B	20	HQ	AJ		14-6	SPARE	D39927		11		D08056J	13			YC051-YR319
2001B	20	HQ	AJ		14-7	SPARE	D39927		11		D08056J	13			YR320-YR328
2001R	20	HQ	AJ		0-0	SPARE	D39927		24		D08056J	12			ALL
2001Z			AJ		0-0	SPARE	D39927		S/R		D08056J	S/R			ALL
2002B	20	HQ	AK		14-6	SPARE	D39927		10		D08056J	10			YC051-YR319
2002B	20	HQ	AK		14-7	SPARE	D39927		10		D08056J	10			YR320-YR328
2002R	20	HQ	AK		0-0	SPARE	D39927		2		D08056J	2			ALL
2002Z			AK		0-0	SPARE	D39927		S/R		D08056J	S/R			ALL
2003B	20	HQ	AL		14-6	SPARE	D39927		15		D08056J	14			YC051-YR319
2003B	20	HQ	AL		14-7	SPARE	D39927		15		D08056J	14			YR320-YR328
2003R	20	HQ	AL		0-0	SPARE	D39927		16		D08056J	4			ALL
2003Z			AL		0-0	SPARE	D39927		S/R		D08056J	S/R			ALL
2004B	20	HX	AM		14-6	77-12-11	D39927		39		D08056J	16			YC051-YR319
2004B	20	HX	AM		14-7	77-12-11	D39927		39		D08056J	16			YR320-YR328
2004R	20	HX	AM		0-0	77-12-11	D39927		19		D08056J	15			ALL
2004Z			AM		0-0	77-12-11	D39927		S/R		D08056J	S/R			ALL
2005R	20	RQ	AN		14-6	77-31-11	D39927		17		D08056J	17			YC051-YD153
2005R	20	RQ	AN		14-6	77-31-11	D39927		6		D08056J	17			YD154-YR319

WIRE LIST

D280A108

91-21-11

Section W1170

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram									
W1178	286A1178			LEADING EDGE-LEFT WING EEC CH A (continued)											
2005R	20	RQ	AN		14-7	77-31-11	D39927		6		D08056J		17		YR320-YR328
2005W	20	RQ	AN		0-0	77-31-11	D39927		18		D08056J		6		YC051-YD153
2005W	20	RQ	AN		0-0	77-31-11	D39927		1		D08056J		6		YD154-YR328
2005ZI			AN		0-0	77-31-11	D39927		7		D08056J		7		ALL
2005ZO			AN		0-0	77-31-11	D39927		S/R		D08056J		S/R		ALL
3001B	20	HR	AP		14-6	79-31-11	D39927		36		D08056J		5		YC051-YR319
3001B	20	HR	AP		14-7	79-31-11	D39927		36		D08056J		5		YR320-YR328
3001R	20	HR	AP		0-0	79-31-11	D39927		35		D08056J		1		ALL
3001Y	20	HR	AP		0-0	79-31-11	D39927		37		D08056J		3		ALL
3001Z			AP		0-0	79-31-11	D39927		S/R		D08056J		S/R		ALL

WIRE LIST

D280A108

91-21-11

Section W1170

Page 7 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Diagram	From				To					
	Wire No.	GA	CO TY			Fam	FT-IN	Equip	Term	Type	Splice	Equip	Term	Type	Splice
W1180	286A1180			LEFT WING/BODY PRESSURE SEAL TO FRONT SPAR INBOARD											
2001B	20	HQ	AP		10-4	27-81-11	D39938	4			SP00520		9		YC051-YC064
2001B	20	HQ	AP		10-5	27-81-11	D39938	4			SP00520		9		YC065-YD153
2001B	20	HQ	AP		10-5	27-81-11	D39938	29			SP00520		9		YD154-YL999, YR301-YR319
2001B	20	HQ	AP		10-4	27-81-11	D39938	29			SP00520		9		YN231-YN501
2001B	20	HQ	AP		10-6	27-81-11	D39938	29			SP00520		9		YR320-YR328
2001R	20	HQ	AP		0-0	27-81-11	D39938	13			SP00588		9		ALL
2001Z			AP		0-0	27-81-11	D39938	S/R			GD04048	ST..	E		ALL
2002B	20	HQ	AQ		10-9	27-81-11	D39938	30			SP00518		9		YC051-YC064, YN231-YN501
2002B	20	HQ	AQ		10-10	27-81-11	D39938	30			SP00518		9		YC065-YL999, YR301-YR328
2002R	20	HQ	AQ		0-0	27-81-11	D39938	31			SP00586		9		ALL
2002Z			AQ		0-0	27-81-11	D39938	S/R			GD04050	ST..	E		ALL
2003B	20	HQ	AR		9-3	27-81-11	D39938	32			SP00522		9		YC051-YC064, YN231-YN501
2003B	20	HQ	AR		9-4	27-81-11	D39938	32			SP00522		9		YC065-YL999, YR301-YR319
2003B	20	HQ	AR		9-5	27-81-11	D39938	32			SP00522		9		YR320-YR328
2003R	20	HQ	AR		0-0	27-81-11	D39938	33			SP00590		9		ALL
2003Z			AR		0-0	27-81-11	D39938	S/R			GD04052	ST..	GW		ALL
2004B	20	HQ	AS		9-3	27-81-11	D39938	15			SP00524		9		YC051-YC064, YN231-YN501
2004B	20	HQ	AS		9-4	27-81-11	D39938	15			SP00524		9		YC065-YL999, YR301-YR319
2004B	20	HQ	AS		9-5	27-81-11	D39938	15			SP00524		9		YR320-YR328
2004R	20	HQ	AS		0-0	27-81-11	D39938	34			SP00592		9		ALL
2004Z			AS		0-0	27-81-11	D39938	S/R			GD04052	ST..	GW		ALL
3001B	18	HR	AA		4-11	28-23-11	D39938	1			D00072		3		YC051-YC064
3001B	18	HR	AA		5-4	28-23-11	D39938	1			D00072		3		YC065-YL999, YR301-YR319
3001B	18	HR	AA		5-3	28-23-11	D39938	1			D00072		3		YN231-YN501
3001B	18	HR	AA		5-5	28-23-11	D39938	1			D00072		3		YR320-YR328
3001R	18	HR	AA		0-0	28-23-11	D39938	3			D00072		1		YC051-YD153
3001R	18	HR	AA		0-0	28-23-11	D39938	9			D00072		1		YD154-YR328
3001Y	18	HR	AA		0-0	28-23-11	D39938	5			D00072		2		YC051-YD153
3001Y	18	HR	AA		0-0	28-23-11	D39938	17			D00072		2		YD154-YR328
3001Z			AA		0-0	28-23-11	D39938	S/R			D00072			AA	ALL
6001	18	HL			3-4	28-23-11	D00072			AA	GD00164	ST..	GW		YC051-YC064

WIRE LIST

D280A108

91-21-11

Section W1180

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1180	286A1180				LEFT WING/BODY PRESSURE SEAL TO FRONT SPAR INBOARD (continued)											
6001	18		HL		2-7	28-23-11		D00072				AA	GD00164	ST..	GW	YC065-YR328
I-B					0-0	27-81-11		S00169		BLU			SP00520		9	ALL
I-R					0-0	27-81-11		S00169		RED			SP00588		9	ALL
I-Y					0-0	27-81-11		S00169		YEL			GD04054	AC..	E	ALL
J-B					0-0	27-81-11		S00168		BLU			SP00518		9	ALL
J-R					0-0	27-81-11		S00168		RED			SP00586		9	ALL
J-Y					0-0	27-81-11		S00168		YEL			GD00614	AC..	E	ALL
K-B					0-0	27-81-11		S00170		BLU			SP00522		9	ALL
K-R					0-0	27-81-11		S00170		RED			SP00590		9	ALL
K-Y					0-0	27-81-11		S00170		YEL			GD00160	AC..	E	ALL
L-B					0-0	27-81-11		S00171		BLU			SP00524		9	ALL
L-R					0-0	27-81-11		S00171		RED			SP00592		9	ALL
L-Y					0-0	27-81-11		S00171		YEL			GD00160	AC..	E	ALL
W1182	286A1182				LEADING EDGE-LEFT WING EEC CH B											
1001R	20		H9	AC	14-11	26-11-11		D39931			9		D30062		5	ALL
1001Z				AC	0-0	26-11-11		D39931		S/R			D30062		S/R	ALL
1002R	20		H9	AD	14-11	26-11-11		D39931			10		D30062		4	ALL
1002Z				AD	0-0	26-11-11		D39931		S/R			D30062		S/R	ALL
1003R	18		H9	AE	12-3	26-12-11		M01762		=B	E		D30062		6	ALL
1003Z				AE	0-0	26-12-11		GD03920		ST..	E		D30062		S/R	ALL
1004	20		HW	AJ	14-11	73-22-11		D39931			7		D30062		21	ALL
1004Z				AJ	0-0	73-22-11		D39931		S/R			D30062		S/R	ALL
1005R	20		H9	AG	2-2	26-12-11		D30062			8		D00834		=1	ALL
1005Z				AG	0-0	26-12-11		D30062		S/R			D00834		DED	ALL
1007	20		HW	AH	14-11	74-11-11		D39931			11		D30062		14	YC051-YD153
1007Z	20		HW	AH	14-11	74-11-11		D39931			6		D30062		14	YD154-YR328
1007Z				AH	0-0	74-11-11		D39931		S/R			D30062		S/R	ALL
2001B	20		HQ	AA	14-11	SPARE		D39931			2		D30062		16	ALL
2001R	20		HQ	AA	0-0	SPARE		D39931			3		D30062		15	ALL
2001Z				AA	0-0	SPARE		D39931		S/R			D30062		S/R	ALL
2002B	20		HQ	AB	14-11	SPARE		D39931			4		D30062		18	ALL
2002R	20		HQ	AB	0-0	SPARE		D39931			5		D30062		17	ALL
2002Z				AB	0-0	SPARE		D39931		S/R			D30062		S/R	ALL
W1184	286A1184				LEADING EDGE-LEFT WING IDG CONTROLS											
1001	20		HP	AA	13-8	29-11-11		D39935			30		D30014		25	YC051-YD153
1001	20		HP	AA	13-8	29-11-11		D39935			18		D30014		25	YD154-YD158, YL951-YR328

WIRE LIST
D280A108

91-21-11
Section W1180
Page 2
Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W1184	286A1184				LEADING EDGE-LEFT WING IDG CONTROLS (continued)												
1001Z				AA	0-0	29-11-11		D39935		S/R		D30014		S/R		YC051-YD158, YL951-YR328	
1002	18	HP	AB		13-8	24-11-11		D39935		10		D30014		17		YC051-YD153	
1002	18	HP	AB		13-9	24-11-11		D39935		10		D30014		17		YD154-YD158, YN231	
1002	18	HP	AB		13-10	24-11-11		D39935		10		D30014		7		YL951-YL999, YN232-YR328	
1002Z				AB	0-0	24-11-11		D39935		S/R		D30014		S/R		YC051-YD158, YL951-YR328	
1003	20	HP	AC		14-7	80-11-11		D39911		11		D30014		18		YC051-YD158, YL951-YR322	
1003	20	HP	AC		14-8	80-11-11		D39911		11		D30014		18		YR323-YR328	
1003Z				AC	0-0	80-11-11		D39911		S/R		D30014		S/R		YC051-YD158, YL951-YR328	
1004	20	HP	AD		14-7	76-21-11		D39911		10		D30014		39		YC051-YD158, YL951-YR322	
1004	20	HP	AD		14-8	76-21-11		D39911		10		D30014		39		YR323-YR328	
1004Z				AD	0-0	76-21-11		D39911		S/R		D30014		S/R		YC051-YD158, YL951-YR328	
1005	20	HP	AE		14-7	80-11-11		D39911		7		D30014		38		YC051-YD158, YL951-YR322	
1005	20	HP	AE		14-8	80-11-11		D39911		7		D30014		38		YR323-YR328	
1005Z				AE	0-0	80-11-11		D39911		S/R		D30014		S/R		YC051-YD158, YL951-YR328	
2001B	20	HQ	AF		13-8	SPARE		D39935		26		D30014		21		YC051-YD153	
2001B	20	HQ	AF		13-9	SPARE		D39935		26		D30014		21		YD154-YD158, YN231	
2001B	20	HQ	AF		13-10	SPARE		D39935		26		D30014		30		YL951-YL999, YN232-YR328	
2001R	20	HQ	AF		0-0	SPARE		D39935		25		D30014		20		YC051-YD158, YN231	
2001R	20	HQ	AF		0-0	SPARE		D39935		25		D30014		32		YL951-YL999, YN232-YR328	
2001Z				AF	0-0	SPARE		D39935		S/R		D30014		S/R		YC051-YD158, YL951-YR328	
2002B	20	HQ	AG		13-8	24-11-11		D39935		39		D30014		2		YC051-YD153	
2002B	20	HQ	AG		13-9	24-11-11		D39935		39		D30014		2		YD154-YD158, YN231	
2002B	20	HQ	AG		13-10	24-11-11		D39935		39		D30014		9		YL951-YL999, YN232-YR328	
2002R	20	HQ	AG		0-0	24-11-11		D39935		19		D30014		10		YC051-YD158, YL951-YR328	

WIRE LIST

D280A108

91-21-11

Section W1180

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1184	286A1184			LEADING EDGE-LEFT WING IDG CONTROLS (continued)											
2002Z				AG	0-0	24-11-11	D39935		S/R		D30014		S/R		YC051-YD158, YL951-YR328
2003B	20	HX	AH		14-7	77-12-21	D39911		3		D30014		29		YC051-YD158, YL951-YR322
2003B	20	HX	AH		14-8	77-12-21	D39911		3		D30014		29		YR323-YR328
2003R	20	HX	AH		0-0	77-12-21	D39911		4		D30014		30		YC051-YD158, YN231
2003R	20	HX	AH		0-0	77-12-21	D39911		4		D30014		21		YL951-YL999, YN232-YR328
2003Z				AH	0-0	77-12-21	D39911		S/R		D30014		S/R		YC051-YD158, YL951-YR328
2004B	20	HQ	AJ		14-7	SPARE	D39911		6		D30014		37		YC051-YD158, YL951-YR322
2004B	20	HQ	AJ		14-8	SPARE	D39911		6		D30014		37		YR323-YR328
2004R	20	HQ	AJ		0-0	SPARE	D39911		5		D30014		36		YC051-YD158, YL951-YR328
2004Z				AJ	0-0	SPARE	D39911		S/R		D30014		S/R		YC051-YD158, YL951-YR328
2005B	20	HQ	AK		14-7	76-21-11	D39911		8		D30014		19		YC051-YD158, YL951-YR322
2005B	20	HQ	AK		14-8	76-21-11	D39911		8		D30014		19		YR323-YR328
2005R	20	HQ	AK		0-0	76-21-11	D39911		9		D30014		8		YC051-YD158, YL951-YR328
2005Z				AK	0-0	76-21-11	D39911		S/R		D30014		S/R		YC051-YD158, YL951-YR328
2006B	20	M2	AM		13-8	24-21-11	D39935		38		D30014		4		YC051-YD153
2006B	20	M2	AM		13-9	24-21-11	D39935		38		D30014		4		YD154-YD158, YN231
2006B	20	M2	AM		13-10	24-21-11	D39935		38		D30014		24		YL951-YL999, YN232-YR328
2006R	20	M2	AM		0-0	24-21-11	D39935		37		D30014		1		YC051-YD158, YL951-YR328
2006ZI				AM	0-0	24-21-11	D39935		36	18	D30014		11	18	YC051-YD158, YL951-YR328
2006ZO				AM	0-0	24-21-11	D39935		S/R		D30014		S/R		YC051-YD158, YL951-YR328
3001B	18	M3	AN		13-8	24-21-11	D39935		17		D30014		14		YC051-YD153
3001B	18	M3	AN		13-9	24-21-11	D39935		12		D30014		14		YD154-YD158, YN231
3001B	18	M3	AN		13-10	24-21-11	D39935		12		D30014		14		YL951-YL999, YN232-YR328
3001R	18	M3	AN		0-0	24-21-11	D39935		6		D30014		12		YC051-YD153

WIRE LIST

D280A108

91-21-11

Section W1180

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	FT-IN	Diagram	From				To				Effectivity	
	GA	CO	TY				Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W1184	286A1184			LEADING EDGE-LEFT WING IDG CONTROLS (continued)												
3001R	18	M3	AN		0-0	24-21-11	D39935		1			D30014	12		YD154-YD158, YL951-YR328	
3001Y	18	M3	AN		0-0	24-21-11	D39935		16			D30014	5		YC051-YD153	
3001Y	18	M3	AN		0-0	24-21-11	D39935		14			D30014	5		YD154-YD158,	YN231
3001Y	18	M3	AN		0-0	24-21-11	D39935		14			D30014	16		YL951-YL999, YN232-YR328	
3001ZI			AN		0-0	24-21-11	D39935		5			D30014	13	18	YC051-YD158,	YN231
3001ZI			AN		0-0	24-21-11	D39935		5			D30014	23	18	YL951-YL999, YN232-YR328	
3001ZO			AN		0-0	24-21-11	D39935		S/R			D30014	S/R		YC051-YD158, YL951-YR328	
4001B	20	HS	AL		13-8	24-24-11	D39935		33			D30014	33		YC051-YD153	
4001B	20	HS	AL		13-9	24-24-11	D39935		15			D30014	33		YD154-YD158,	YN231
4001B	20	HS	AL		13-10	24-24-11	D39935		15			D30014	33		YL951-YL999, YN232-YR328	
4001G	20	HS	AL		0-0	24-24-11	D39935		15			D30014	15		YC051-YD153	
4001G	20	HS	AL		0-0	24-24-11	D39935		33			D30014	15		YD154-YD158,	YN231
4001G	20	HS	AL		0-0	24-24-11	D39935		33			D30014	22		YL951-YL999, YN232-YR328	
4001R	20	HS	AL		0-0	24-24-11	D39935		34			D30014	31		YC051-YD153	
4001R	20	HS	AL		0-0	24-24-11	D39935		35			D30014	31		YD154-YD158,	YN231
4001R	20	HS	AL		0-0	24-24-11	D39935		35			D30014	34		YL951-YL999, YN232-YR328	
4001Y	20	HS	AL		0-0	24-24-11	D39935		35			D30014	32		YC051-YD153	
4001Y	20	HS	AL		0-0	24-24-11	D39935		32			D30014	32		YD154-YD158,	YN231
4001Y	20	HS	AL		0-0	24-24-11	D39935		32			D30014	20		YL951-YL999, YN232-YR328	
4001Z			AL		0-0	24-24-11	D39935		S/R			D30014	S/R		YC051-YD158, YL951-YR328	
W1186	286A1186			LEADING EDGE-LEFT WING-POWER FEEDER												
0001	02	HA			2-4	24-21-11	D08094J		A			SM00001		GX		YC051-YC059
0001	02	HA			2-6	24-21-11	D08094J		A			SM00001		GX		YC060-YR328
0002	02	HA			2-5	24-21-11	D08094J		B			SM00002		GX		YC051-YC059
0002	02	HA			2-6	24-21-11	D08094J		B			SM00002		GX		YC060-YR328
0003	02	HA			2-7	24-21-11	D08094J		C			SM00003		GX		YC051-YC059
0003	02	HA			2-5	24-21-11	D08094J		C			SM00003		GX		YC060-YR328
0004	04	HA			2-6	24-21-11	D08094J		D			GD03834	AC..	IA		ALL
0005	*1	QY			49-9	24-21-11	TB5001		A	H1		SM00001		GX		YC051-YL964

WIRE LIST

D280A108

91-21-11

Section W1180

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W1186	286A1186				LEADING EDGE-LEFT WING-POWER FEEDER (continued)											
0005	*1		QY		50-2		24-21-11	TB5001		A	H1	SM00001		GX		YL965-YL999, YR301-YR328
0005	*1		QY		39-7		24-21-11	TB5001		A	H1	SM00001		GX		YN231-YN235
0005	*1		QY		40-1		24-21-11	TB5001		A	H1	SM00001		GX		YN236-YN501
0006	*1		QY		49-8		24-21-11	TB5001		B	H1	SM00002		GX		YC051-YL999, YR301-YR328
0006	*1		QY		39-6		24-21-11	TB5001		B	H1	SM00002		GX		YN231-YN235
0006	*1		QY		39-7		24-21-11	TB5001		B	H1	SM00002		GX		YN236-YN501
0007	*1		QY		49-7		24-21-11	TB5001		C	H1	SM00003		GX		YC051-YL964
0007	*1		QY		49-5		24-21-11	TB5001		C	H1	SM00003		GX		YL965-YL999, YR301-YR328
0007	*1		QY		39-4		24-21-11	TB5001		C	H1	SM00003		GX		YN231-YN235
0007	*1		QY		39-3		24-21-11	TB5001		C	H1	SM00003		GX		YN236-YN501
W1188	286A1188				LEFT WING/BODY PRESSURE SEAL TO FRONT SPAR OUTBD											
1012	20		HP	AM	20-9		30-11-11	D39903		10		D00738		1		YC051-YD153
1012	20		HP	AM	20-9		30-11-11	D39903		2		D00738		1		YD154-YR319
1012	20		HP	AM	20-10		30-11-11	D39903		2		D00738		1		YR320-YR328
1012Z				AM	0-0		30-11-11	D39903		S/R		D00738		S/R		ALL
1013	20		HP	AN	1-9		30-11-11	D00738		2		GD03980		DC..	E	*1 YC051-YD158
1013	20		HP	AN	2-1		30-11-11	D00738		2		GD03980		DC..	E	*1 YD160-YR319
1013	20		HP	AN	2-2		30-11-11	D00738		2		GD03980		DC..	E	*1 YR320-YR328
1013Z				AN	0-0		30-11-11	D00738		S/R		GD03980		DC..	E	*1 ALL
1014R	18		H9	BB	19-8		26-12-11	D39903		14		M01762		= A	E	YC051-YD153
1014R	18		H9	BB	19-8		26-12-11	D39903		1		M01762		= A	E	YD154-YR319
1014R	18		H9	BB	19-9		26-12-11	D39903		1		M01762		= A	E	YR320-YR328
1014Z				BB	0-0		26-12-11	D39903		S/R		GD03920		ST..	E	ALL
2005B	20		HQ	AT	64-0		27-81-12	D39903		36		SP02876			9	YC051-YD158
2005B	20		HQ	AT	64-2		27-81-12	D39903		36		SP02876			9	YD160-YR319
2005B	20		HQ	AT	64-3		27-81-12	D39903		36		SP02876			9	YR320-YR328
2005R	20		HQ	AT	0-0		27-81-12	D39903		35		SP01948			9	ALL
2005Z				AT	0-0		27-81-12	D39903		S/R		GD04064		ST..	E	ALL
2006B	20		HQ	AU	58-6		27-81-12	D39903		28		SP02886			9	YC051-YD158
2006B	20		HQ	AU	58-7		27-81-12	D39903		28		SP02886			9	YD160-YR319
2006B	20		HQ	AU	58-8		27-81-12	D39903		28		SP02886			9	YR320-YR328
2006R	20		HQ	AU	0-0		27-81-12	D39903		27		SP02884			9	ALL
2006Z				AU	0-0		27-81-12	D39903		S/R		GD04066		ST..	E	ALL
2007B	20		HQ	AV	49-2		27-81-12	D39903		38		SP02938			9	YC051-YD158
2007B	20		HQ	AV	49-3		27-81-12	D39903		38		SP02938			9	YD160-YR319

WIRE LIST

D280A108

91-21-11

Section W1180

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Diagram	From				To				Effectivity		
	Wire No.	GA	CO TY			Fam	FT-IN	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W1188	286A1188			LEFT WING/BODY PRESSURE SEAL TO FRONT SPAR OUTBD (continued)												
2007B	20	HQ	AV		49-4	27-81-12	D39903		38			SP02938		9	YR320-YR328	
2007R	20	HQ	AV		0-0	27-81-12	D39903		37			SP02936		9	ALL	
2007Z			AV		0-0	27-81-12	D39903		S/R			GD04068	ST..	E	ALL	
2008B	20	HQ	AW		45-4	27-81-12	D39903		18			SP02942		9	YC051-YR319	
2008B	20	HQ	AW		45-5	27-81-12	D39903		18			SP02942		9	YR320-YR328	
2008R	20	HQ	AW		0-0	27-81-12	D39903		39			SP02940		9	ALL	
2008Z			AW		0-0	27-81-12	D39903		S/R			GD04070	ST..	E	ALL	
2009B	20	HQ	AX		37-8	27-81-12	D39903		19			SP03362		9	YC051-YD158	
2009B	20	HQ	AX		37-9	27-81-12	D39903		19			SP03362		9	YD160-YR319	
2009B	20	HQ	AX		37-10	27-81-12	D39903		19			SP03362		9	YR320-YR328	
2009R	20	HQ	AX		0-0	27-81-12	D39903		8			SP02944		9	ALL	
2009Z			AX		0-0	27-81-12	D39903		S/R			GD04080	ST..	E	ALL	
2010B	20	HQ	AY		34-2	27-81-12	D39903		21			SP03422		9	YC051-YD158	
2010B	20	HQ	AY		34-3	27-81-12	D39903		21			SP03422		9	YD160-YR319	
2010B	20	HQ	AY		34-4	27-81-12	D39903		21			SP03422		9	YR320-YR328	
2010R	20	HQ	AY		0-0	27-81-12	D39903		20			SP03380		9	ALL	
2010Z			AY		0-0	27-81-12	D39903		S/R			GD04082	ST..	E	ALL	
2011B	20	HQ	AZ		26-9	27-81-12	D39903		23			SP03430		9	YC051-YD158	
2011B	20	HQ	AZ		26-10	27-81-12	D39903		23			SP03430		9	YD160-YR319	
2011B	20	HQ	AZ		26-11	27-81-12	D39903		23			SP03430		9	YR320-YR328	
2011R	20	HQ	AZ		0-0	27-81-12	D39903		22			SP03428		9	ALL	
2011Z			AZ		0-0	27-81-12	D39903		S/R			GD04084	ST..	E	ALL	
2012B	20	HQ	BA		23-6	27-81-12	D39903		25			SP03436		9	YC051-YD158	
2012B	20	HQ	BA		23-7	27-81-12	D39903		25			SP03436		9	YD160-YR319	
2012B	20	HQ	BA		23-8	27-81-12	D39903		25			SP03436		9	YR320-YR328	
2012R	20	HQ	BA		0-0	27-81-12	D39903		24			SP03432		9	ALL	
2012Z			BA		0-0	27-81-12	D39903		S/R			GD04086	ST..	E	ALL	
2601B	20	HQ	SA		46-1	27-81-12	D39903		12			D10589		2	YC051-YR319	
2601B	20	HQ	SA		46-2	27-81-12	D39903		12			D10589		2	YR320-YR328	
2601R	20	HQ	SA		0-0	27-81-12	D39903		11			D10589		1	ALL	
2601Z			SA		0-0	27-81-12	D39903		S/R			D10589	S/R		ALL	
2602B	20	HQ	SB		34-9	27-81-12	D39903		16			D10591		2	YC051-YD158	
2602B	20	HQ	SB		34-10	27-81-12	D39903		16			D10591		2	YD160-YR319	
2602B	20	HQ	SB		34-11	27-81-12	D39903		16			D10591		2	YR320-YR328	
2602R	20	HQ	SB		0-0	27-81-12	D39903		15			D10591		1	ALL	
2602Z			SB		0-0	27-81-12	D39903		S/R			D10591	S/R		ALL	
2603B	20	HQ	SC		23-11	27-81-12	D39903		30			D10593		2	YC051-YD158	
2603B	20	HQ	SC		24-1	27-81-12	D39903		30			D10593		2	YD160-YR319	
2603B	20	HQ	SC		24-2	27-81-12	D39903		30			D10593		2	YR320-YR328	

WIRE LIST

D280A108

91-21-11

Section W1180

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice Effectivity

W1188		286A1188	LEFT WING/BODY PRESSURE SEAL TO FRONT SPAR OUTBD (continued)											
2603R	20	HQ	SC	0-0	27-81-12	D39903	29	D10593	1					ALL
2603Z			SC	0-0	27-81-12	D39903	S/R	D10593	S/R					ALL
A-B				0-0	27-81-12	S00994	BLU	SP02876		9				ALL
A-R				0-0	27-81-12	S00994	RED	SP01948		9				ALL
A-Y				0-0	27-81-12	S00994	YEL	GD04056	AC..	E				ALL
B-B				0-0	27-81-12	S00995	BLU	SP02886		9				ALL
B-R				0-0	27-81-12	S00995	RED	SP02884		9				ALL
B-Y				0-0	27-81-12	S00995	YEL	GD04058	AC..	E				ALL
C-B				0-0	27-81-12	S00996	BLU	SP02938		9				ALL
C-R				0-0	27-81-12	S00996	RED	SP02936		9				ALL
C-Y				0-0	27-81-12	S00996	YEL	GD04060	AC..	E				ALL
D-B				0-0	27-81-12	S00997	BLU	SP02942		9				ALL
D-R				0-0	27-81-12	S00997	RED	SP02940		9				ALL
D-Y				0-0	27-81-12	S00997	YEL	GD04062	AC..	E				ALL
E-B				0-0	27-81-12	S00998	BLU	SP03362		9				ALL
E-R				0-0	27-81-12	S00998	RED	SP02944		9				ALL
E-Y				0-0	27-81-12	S00998	YEL	GD04072	AC..	E				ALL
F-B				0-0	27-81-12	S00999	BLU	SP03422		9				ALL
F-R				0-0	27-81-12	S00999	RED	SP03380		9				ALL
F-Y				0-0	27-81-12	S00999	YEL	GD04074	AC..	E				ALL
G-B				0-0	27-81-12	S01000	BLU	SP03430		9				ALL
G-R				0-0	27-81-12	S01000	RED	SP03428		9				ALL
G-Y				0-0	27-81-12	S01000	YEL	GD04076	AC..	E				ALL
H-B				0-0	27-81-12	S01001	BLU	SP03436		9				ALL
H-R				0-0	27-81-12	S01001	RED	SP03432		9				ALL
H-Y				0-0	27-81-12	S01001	YEL	GD04078	AC..	E				ALL

WIRE LIST

D280A108

91-21-11

Section W1180

Page 8 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1242	286A1242			L LEADING EDGE TO WING TIP											
1001	12	HE	AA		3-9	33-43-11	D11046	8			D40014J	1			ALL
1001Z			AA		0-0	33-43-11	D11046	S/R			D40014J	S/R			ALL
1002	12	HE	AB		3-9	33-43-11	D11046	3			D40014J	2			ALL
1002Z			AB		0-0	33-43-11	D11046	S/R			D40014J	S/R			ALL
1003	12	HE	AC		3-9	33-43-11	D11046	7			D40014J	3			ALL
1003Z			AC		0-0	33-43-11	D11046	S/R			D40014J	S/R			ALL
1004	12	HE	AD		5-1	33-43-11	GD03898	AC..	N	*1	D40014J	4			ALL
1004Z			AD		0-0	33-43-11	D40014J	S/R			GD03898	AC..	N	*1	ALL
1006	12	HE	AF		3-6	33-43-11	GD03898	AC..	N	*2	D11046	1			ALL
1006Z			AF		0-0	33-43-11	D11046	S/R			GD03898	AC..	N	*2	ALL
1007	12	HE	AG		2-4	33-43-11	D11046	5			GD03892	ST..	N	*1	ALL
1007Z			AG		0-0	33-43-11	D11046	S/R			GD03892	ST..	N	*1	ALL
1021	20	HE	AV		4-1	33-44-12	D11042	2			GD03898	AC..	N	*3	ALL
1021Z			AV		0-0	33-44-12	D11042	S/R			GD03898	AC..	N	*3	ALL
1022	20	HE	AW		2-10	33-44-12	D11042	3			GD03900	ST..	N	*	ALL
1022Z			AW		0-0	33-44-12	D11042	S/R			GD03900	ST..	N	*	ALL
W1244	286A1244			R LEADING EDGE TO WING TIP											
1001	12	HE	AA		3-10	33-43-11	D11044	8			D40016J	1			ALL
1001Z			AA		0-0	33-43-11	D11044	S/R			D40016J	S/R			ALL
1002	12	HE	AB		3-10	33-43-11	D11044	3			D40016J	2			ALL
1002Z			AB		0-0	33-43-11	D11044	S/R			D40016J	S/R			ALL
1003	12	HE	AC		3-10	33-43-11	D11044	7			D40016J	3			ALL
1003Z			AC		0-0	33-43-11	D11044	S/R			D40016J	S/R			ALL
1004	12	HE	AD		5-2	33-43-11	GD03902	AC..	N	*1	D40016J	4			ALL
1004Z			AD		0-0	33-43-11	D40016J	S/R			GD03902	AC..	N	*1	ALL
1006	12	HE	AF		3-5	33-43-11	GD03902	AC..	N	*2	D11044	1			ALL
1006Z			AF		0-0	33-43-11	D11044	S/R			GD03902	AC..	N	*2	ALL
1007	12	HE	AG		2-4	33-43-11	D11044	5			GD03896	ST..	N	*	ALL
1007Z			AG		0-0	33-43-11	D11044	S/R			GD03896	ST..	N	*	ALL
1021	20	HE	AV		4-4	33-44-12	D11040	2			GD03902	AC..	N	*3	ALL
1021Z			AV		0-0	33-44-12	D11040	S/R			GD03902	AC..	N	*3	ALL
1022	20	HE	AW		3-1	33-44-12	D11040	3			GD03904	ST..	N	*	ALL
1022Z			AW		0-0	33-44-12	D11040	S/R			GD03904	ST..	N	*	ALL

WIRE LIST

D280A108

91-21-11

Section W1240

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From			To			Effectivity		
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W1262	286A1262			ENGINE STRUT-RIGHT FIREWALL TO AW0258R POWER FEEDER											
0001	*1		HA		8-4	24-21-21	D08194P		A		D30438		A		YC051-YC059
0001	*1		HA		9-0	24-21-21	D08194P		A		D30438		A		YC060-YR328
0002	*1		HA		8-4	24-21-21	D08194P		B		D30438		B		YC051-YC059
0002	*1		HA		9-0	24-21-21	D08194P		B		D30438		B		YC060-YR328
0003	*1		HA		8-4	24-21-21	D08194P		C		D30438		C		YC051-YC059
0003	*1		HA		9-0	24-21-21	D08194P		C		D30438		C		YC060-YR328
0004	04		HA		8-4	24-21-21	D08194P		D		D30438		D		YC051-YC059
0004	04		HA		9-0	24-21-21	D08194P		D		D30438		D		YC060-YR328
W1264	286A1264			ENGINE STRUT-RIGHT FIREWALL TO AW0258R IDG CONTROLS											
0001	20		HL		1-9	80-11-11	D30434		39		GD03936	DC..	1		ALL
0002	20		HL		3-10	80-11-11	D30434		21		GD03928	ST..	1		YC051-YC054
0002	20		HL		1-9	80-11-11	D30434		21		GD03936	ST..	1		YC055-YR328
0003	20		HL		1-9	80-11-11	D30434		9		GD03936	DC..	1		ALL
0005	20		HL		1-9	29-11-11	D30434		19		GD03936	DC..	1		ALL
0006	20		HL		1-9	76-21-21	D30434		42		GD03936	DC..	1		ALL
0007	20		HL		1-9	76-21-21	D30434		23		GD03936	DC..	1		ALL
1003	20		HP	AA	12-11	80-11-11	D30116		18		D30434		38		ALL
1003Z				AA	0-0	80-11-11	D30116		S/R		D30434		S/R		ALL
1005	20		HP	AB	12-11	80-11-11	D30116		38		D30434		22		ALL
1005Z				AB	0-0	80-11-11	D30116		S/R		D30434		S/R		ALL
1006	20		HP	AE	12-11	76-21-21	D30116		39		D30434		40		ALL
1006Z				AE	0-0	76-21-21	D30116		S/R		D30434		S/R		ALL
1009	20		HP	AJ	13-0	29-11-11	D30116		25		D30434		36		ALL
1009Z				AJ	0-0	29-11-11	D30116		S/R		D30434		S/R		ALL
1011	18		HP	AM	12-11	24-11-21	D30116		17		D30434		25		YC051-YD158, YN231
1011	18		HP	AM	12-11	24-11-21	D30116		7		D30434		25		YD160-YL999, YN232-YR328
1011Z				AM	0-0	24-11-21	D30116		S/R		D30434		S/R		ALL
1012	18		HP	AU	1-9	24-11-21	D30434		11		GD03936	DC..	1		ALL
1012Z				AU	0-0	24-11-21	D30434		S/R		GD03936		DED		ALL
2001B	20		HQ	AD	12-11	77-12-21	D30116		29		D30434		5		ALL
2001R	20		HQ	AD	0-0	77-12-21	D30116		30		D30434		15		YC051-YD158, YN231
2001R	20		HQ	AD	0-0	77-12-21	D30116		21		D30434		15		YD160-YL999, YN232-YR328
2001Z				AD	0-0	77-12-21	D30116		S/R		D30434		S/R		ALL
2002B	20		HQ	AH	12-11	76-21-21	D30116		19		D30434		24		ALL
2002R	20		HQ	AH	0-0	76-21-21	D30116		8		D30434		41		ALL
2002Z				AH	0-0	76-21-21	D30116		S/R		D30434		S/R		ALL

WIRE LIST

D280A108

91-21-11

Section W1260

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W1264	286A1264			ENGINE STRUT-RIGHT FIREWALL TO AW0258R IDG CONTROLS (continued)										
2003B	20	HQ	AL	12-11	24-11-21	D30116		2		D30434	31		YC051-YD158, YN231	
2003B	20	HQ	AL	12-11	24-11-21	D30116		9		D30434	31		YD160-YL999, YN232-YR328	
2003R	20	HQ	AL	0-0	24-11-21	D30116		10		D30434	32		ALL	
2003Z			AL	0-0	24-11-21	D30116		S/R		D30434	S/R		ALL	
2004B	20	HQ	AP	12-11	24-21-21	D30116		4		D30434	33		YC051-YD158, YN231	
2004B	20	HQ	AP	12-11	24-21-21	D30116		24		D30434	33		YD160-YL999, YN232-YR328	
2004R	20	HQ	AP	0-0	24-21-21	D30116		1		D30434	34		ALL	
2004Z			AP	0-0	24-21-21	D30116		11	18	D30434	17		ALL	
2005B	20	HQ	AS	12-11	SPARE	D30116		21		D30434	26		YC051-YD158, YN231	
2005B	20	HQ	AS	12-11	SPARE	D30116		30		D30434	26		YD160-YL999, YN232-YR328	
2005R	20	HQ	AS	0-0	SPARE	D30116		20		D30434	12		YC051-YD158, YN231	
2005R	20	HQ	AS	0-0	SPARE	D30116		32		D30434	12		YD160-YL999, YN232-YR328	
2005Z			AS	0-0	SPARE	D30116		S/R		D30434	S/R		ALL	
2006B	20	HQ	AT	12-11	SPARE	D30116		37		D30434	37		ALL	
2006R	20	HQ	AT	0-0	SPARE	D30116		36		D30434	20		ALL	
2006Z			AT	0-0	SPARE	D30116		S/R		D30434	S/R		ALL	
3001B	18	HR	AQ	12-11	24-21-21	D30116		14		D30434	8		ALL	
3001R	18	HR	AQ	0-0	24-21-21	D30116		12		D30434	3		ALL	
3001Y	18	HR	AQ	0-0	24-21-21	D30116		5		D30434	6		YC051-YD158, YN231	
3001Y	18	HR	AQ	0-0	24-21-21	D30116		16		D30434	6		YD160-YL999, YN232-YR328	
3001Z			AQ	0-0	24-21-21	D30116		13	18	D30434	2		YC051-YD158, YN231	
3001Z			AQ	0-0	24-21-21	D30116		23	18	D30434	2		YD160-YL999, YN232-YR328	
4001B	20	HS	AR	12-11	24-24-21	D30116		33		D30434	28		ALL	
4001G	20	HS	AR	0-0	24-24-21	D30116		15		D30434	29		YC051-YD158, YN231	
4001G	20	HS	AR	0-0	24-24-21	D30116		22		D30434	29		YD160-YL999, YN232-YR328	
4001R	20	HS	AR	0-0	24-24-21	D30116		31		D30434	13		YC051-YD158, YN231	
4001R	20	HS	AR	0-0	24-24-21	D30116		34		D30434	13		YD160-YL999, YN232-YR328	
4001Y	20	HS	AR	0-0	24-24-21	D30116		32		D30434	27		YC051-YD158, YN231	
4001Y	20	HS	AR	0-0	24-24-21	D30116		20		D30434	27		YD160-YL999, YN232-YR328	
4001Z			AR	0-0	24-24-21	D30116		S/R		D30434	S/R		ALL	

WIRE LIST

D280A108

91-21-11

Section W1260

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		Diagram	From			To					
	Wire No.	GA	CO TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W1266	286A1266			ENGINE STRUT-RIGHT FIREWALL TO AW0258R EEC CH B												
0001	20		HL		1-7	74-11-11		D30456		1		GD03940	AC..	1		ALL
0002	20		HL		1-7	73-22-11		D30456		7		GD03940	AC..	1		ALL
0010	18		HL		3-1	26-12-11		GD03942	ST..	GW		GD03928	ST..	1		YC051-YC054
0010	18		HL		4-4	26-12-11		GD03942	ST..	GW		GD03940	ST..	1		YC055-YR328
1001	20		HP	AA	12-4	74-11-11		D30164		14		D30456		6		ALL
1001Z				AA	0-0	74-11-11		D30164		S/R		D30456		S/R		ALL
1003R	20		H9	AC	11-11	26-11-21		D30164		5		D30420		3		YC051-YC054
1003R	20		H9	AC	11-10	26-11-21		D30164		5		D30420		3		YC055-YR328
1003Z				AC	0-0	26-11-21		D30164		S/R		D30420		S/R		ALL
1004R	20		H9	AD	11-11	26-11-21		D30164		4		D30420		4		YC051-YC054
1004R	20		H9	AD	11-10	26-11-21		D30164		4		D30420		4		YC055-YR328
1004Z				AD	0-0	26-11-21		D30164		S/R		D30420		S/R		ALL
1005R	18		9L	AE	10-0	26-12-11		D30164		6	18	M01763	=A	GW		ALL
1005Z				AE	0-0	26-12-11		D30164		S/R		M01763			FA	ALL
1006R	18		9L	AF	10-0	26-12-11		D30164		8	18	M01763	=B	GW		ALL
1006Z				AF	0-0	26-12-11		D30164		S/R		M01763			FA	ALL
1008	20		HP	AH	12-4	73-22-11		D30164		21		D30456		2		ALL
1008Z				AH	0-0	73-22-11		D30164		S/R		D30456		S/R		ALL
2001B	20		HQ	AK	11-11	SPARE		D30164		16		D30420		2		YC051-YC054
2001B	20		HQ	AK	11-10	SPARE		D30164		16		D30420		2		YC055-YR328
2001R	20		HQ	AK	0-0	SPARE		D30164		15		D30420		1		ALL
2001Z				AK	0-0	SPARE		D30164		S/R		D30420		S/R		ALL
2002B	20		HQ	AL	12-4	SPARE		D30164		18		D30456		4		ALL
2002R	20		HQ	AL	0-0	SPARE		D30164		17		D30456		3		ALL
2002Z				AL	0-0	SPARE		D30164		S/R		D30456		S/R		ALL
FRAA					0-0	26-12-11		M01763			FA	GD03942	ST..	GW		ALL
W1268	286A1268			ENGINE STRUT-RIGHT FIREWALL TO AW0258R EEC CH B												
0002	20		GK		0-7	73-21-11		D30460		36		D30460		19		YN231-YN501
0012	20		HL		0-7	73-21-11		D30460		36		D30460		20		YC056-YC058
0012	20		GK		0-7	73-21-11		D30460		36		D30460		20		YC059-YL999, YR301-YR328
1001	20		E4	AB	7-4	31-35-05		D30184		1		D00528		3		YL963-YL999, YN236-YR328
1001Z				AB	0-0	31-35-05		D30184		PERB		D00528		PERB		YL963-YL999, YN236-YR328
1014	20		HP	BB	12-8	36-11-11		D30184		3		D30404		3		YC056-YC058
1014	20		E4	BB	12-8	36-11-11		D30184		3		D30404		3		YC059-YR328
1014Z				BB	0-0	36-11-11		D30184		PERB		D30404		PERB		YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W1260

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From			To			Effectivity		
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W1268	286A1268			ENGINE STRUT-RIGHT FIREWALL TO AW0258R EEC CH B (continued)											
2003B	20	HQ	AE		12-2	78-35-21	D30460			14		D30408		7	YC056-YC058
2003B	20	E5	AE		12-2	78-35-21	D30460			14		D30408		7	YC059-YR328
2003R	20	HQ	AE		0-0	78-35-21	D30460			5		D30408		6	YC056-YC058
2003R	20	E5	AE		0-0	78-35-21	D30460			5		D30408		6	YC059-YR328
2003Z			AE		0-0	78-35-21	D30460		PERB			D30408	PERB		YC056-YR328
2004B	20	HQ	AG		3-5	78-35-21	D30460			21		D30410		7	YC056-YC058
2004B	20	E5	AG		3-5	78-35-21	D30460			21		D30410		7	YC059-YR328
2004R	20	HQ	AG		0-0	78-35-21	D30460			8		D30410		6	YC056-YC058
2004R	20	E5	AG		0-0	78-35-21	D30460			8		D30410		6	YC059-YR328
2004Z			AG		0-0	78-35-21	D30460		PERB			D30410	PERB		YC056-YR328
2007R	20	RJ	AN		12-8	77-31-21	D30184			8		D30404		6	YC056-YR328
2007W	20	RJ	AN		0-0	77-31-21	D30184			18		D30404		7	YC056-YR328
2007Z			AN		0-0	77-31-21	D30184			7		D30404		1	YC056-YR328
2008B	20	HQ	AA		10-4	73-21-11	D30184			23		D30460		10	YC056-YC058
2008B	20	E5	AA		10-4	73-21-11	D30184			23		D30460		10	YC059-YR328
2008R	20	HQ	AA		0-0	73-21-11	D30184			22		D30460		9	YC056-YC058
2008R	20	E5	AA		0-0	73-21-11	D30184			22		D30460		9	YC059-YR328
2008Z			AA		0-0	73-21-11	D30184		PERB			D30460	PERB		YC056-YR328
2009B	20	HQ	AR		10-4	73-21-21	D30184			11		D30460		27	YC056-YC058
2009B	20	E5	AR		10-4	73-21-21	D30184			11		D30460		27	YC059-YR328
2009R	20	HQ	AR		0-0	73-21-21	D30184			26		D30460		13	YC056-YC058
2009R	20	E5	AR		0-0	73-21-21	D30184			26		D30460		13	YC059-YR328
2009Z			AR		0-0	73-21-21	D30184		PERB			D30460	PERB		YC056-YR328
2010B	20	HQ	AS		10-4	73-21-21	D30184			27		D30460		26	YC056-YC058
2010B	20	E5	AS		10-4	73-21-21	D30184			27		D30460		26	YC059-YR328
2010R	20	HQ	AS		0-0	73-21-21	D30184			28		D30460		12	YC056-YC058
2010R	20	E5	AS		0-0	73-21-21	D30184			28		D30460		12	YC059-YR328
2010Z			AS		0-0	73-21-21	D30184		PERB			D30460	PERB		YC056-YR328
2011B	20	HQ	AT		10-4	73-21-21	D30184			25		D30460		25	YC056-YC058
2011B	20	E5	AT		10-4	73-21-21	D30184			25		D30460		25	YC059-YR328
2011R	20	HQ	AT		0-0	73-21-21	D30184			24		D30460		11	YC056-YC058
2011R	20	E5	AT		0-0	73-21-21	D30184			24		D30460		11	YC059-YR328
2011Z			AT		0-0	73-21-21	D30184		PERB			D30460	PERB		YC056-YR328
2012B	20	HQ	AU		10-4	73-24-21	D30184			34		D30460		4	YC056-YC058
2012B	20	E5	AU		10-4	73-24-21	D30184			34		D30460		4	YC059-YR328
2012R	20	HQ	AU		0-0	73-24-21	D30184			15		D30460		1	YC056-YC058
2012R	20	E5	AU		0-0	73-24-21	D30184			15		D30460		1	YC059-YR328
2012Z			AU		0-0	73-24-21	D30184		PERB			D30460	PERB		YC056-YR328
2013B	20	HQ	AV		10-4	73-24-12	D30184			35		D30460		3	YC056-YC058

WIRE LIST

D280A108

91-21-11

Section W1260

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1268	286A1268			ENGINE STRUT-RIGHT FIREWALL TO AW0258R EEC CH B (continued)											
2013B	20	E5	AV		10-4	73-24-12	D30184		35		D30460		3		YC059-YR328
2013R	20	HQ	AV		0-0	73-24-12	D30184		36		D30460		2		YC056-YC058
2013R	20	E5	AV		0-0	73-24-12	D30184		36		D30460		2		YC059-YR328
2013Z			AV		0-0	73-24-12	D30184		PERB		D30460		PERB		YC056-YR328
2015B	20	HQ	BH		12-8	SPARE	D30184		14		D30404		13		YC056-YC058
2015B	20	E5	BH		12-8	SPARE	D30184		14		D30404		13		YC059-YR328
2015R	20	HQ	BH		0-0	SPARE	D30184		5		D30404		4		YC056-YC058
2015R	20	E5	BH		0-0	SPARE	D30184		5		D30404		4		YC059-YR328
2015Z			BH		0-0	SPARE	D30184		PERB		D30404		PERB		YC056-YR328
2016B	20	HQ	BJ		10-4	SPARE	D30184		31		D30460		39		YC056-YC058
2016B	20	E5	BJ		10-4	SPARE	D30184		31		D30460		39		YC059-YR328
2016R	20	HQ	BJ		0-0	SPARE	D30184		30		D30460		22		YC056-YC058
2016R	20	E5	BJ		0-0	SPARE	D30184		30		D30460		22		YC059-YR328
2016Z			BJ		0-0	SPARE	D30184		PERB		D30460		PERB		YC056-YR328
2018B	20	HQ	AZ		12-8	36-11-11	D30184		2		D30404		11		YC056-YC058
2018B	20	E5	AZ		12-8	36-11-11	D30184		2		D30404		11		YC059-YR328
2018R	20	HQ	AZ		0-0	36-11-11	D30184		10		D30404		12		YC056-YC058
2018R	20	E5	AZ		0-0	36-11-11	D30184		10		D30404		12		YC059-YR328
2018Z			AZ		0-0	36-11-11	D30184		PERB		D30404		PERB		YC056-YR328
2019B	20	HQ	BC		9-1	36-11-11	D30404		2		SM00002		V1		YC056-YC058
2019B	20	E5	BC		11-5	36-11-11	D30404		2		SM00002		V1		YC059-YR328
2019R	20	HQ	BC		0-0	36-11-11	D30404		10		SM00001		V1		YC056-YC058
2019R	20	E5	BC		0-0	36-11-11	D30404		10		SM00001		V1		YC059-YR328
2019Z			BC		0-0	36-11-11	D30404		PERB		SM00001		REF	AA	YC056-YR328
2020B	20	HQ	BE		3-3	36-11-11	D00528		1		SM00002		V1		YC056-YC058
2020B	20	E5	BE		6-1	36-11-11	D00528		1		SM00002		V1		YC059-YR328
2020R	20	HQ	BE		0-0	36-11-11	D00528		2		SM00001		V1		YC056-YC058
2020R	20	E5	BE		0-0	36-11-11	D00528		2		SM00001		V1		YC059-YR328
2020Z			BE		0-0	36-11-11	D00528		PERB		SM00001		REF	AA	YC056-YR328
2021B	20	HQ	BD		4-1	36-11-11	D30184		29		SM00002		V1		YC056-YC058
2021B	20	E5	BD		1-9	36-11-11	D30184		29		SM00002		V1		YC059-YR328
2021R	20	HQ	BD		0-0	36-11-11	D30184		12		SM00001		V1		YC056-YC058
2021R	20	E5	BD		0-0	36-11-11	D30184		12		SM00001		V1		YC059-YR328
2021Z			BD		0-0	36-11-11	D30184		PERB		SM00001		REF	AA	YC056-YR328
2022B	20	HQ	AC		10-4	78-35-21	D30184		13		D30460		32		YC056-YC058
2022B	20	E5	AC		10-4	78-35-21	D30184		13		D30460		32		YC059-YR328
2022R	20	HQ	AC		0-0	78-35-21	D30184		4		D30460		33		YC056-YC058
2022R	20	E5	AC		0-0	78-35-21	D30184		4		D30460		33		YC059-YR328
2022Z			AC		0-0	78-35-21	D30184		PERB		D30460		PERB		YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W1260

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From			To			Effectivity		
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W1268	286A1268			ENGINE STRUT-RIGHT FIREWALL TO AW0258R EEC CH B (continued)										
2023B	20	HQ	AP	10-4	73-21-12	D30184	9			D30460	42		YC056-YC058	
2023B	20	E5	AP	10-4	73-21-12	D30184	9			D30460	42		YC059-YR328	
2023R	20	HQ	AP	0-0	73-21-12	D30184	21			D30460	24		YC056-YC058	
2023R	20	E5	AP	0-0	73-21-12	D30184	21			D30460	24		YC059-YR328	
2023Z			AP	0-0	73-21-12	D30184	PERB			D30460	PERB		YC056-YR328	
2024B	20	HQ	AX	12-8	30-11-11	D30184	16			D30404	5		YC056-YC058	
2024B	20	E5	AX	12-8	30-11-11	D30184	16			D30404	5		YC059-YR328	
2024R	20	HQ	AX	0-0	30-11-11	D30184	6			D30404	14		YC056-YC058	
2024R	20	E5	AX	0-0	30-11-11	D30184	6			D30404	14		YC059-YR328	
2024Z			AX	0-0	30-11-11	D30184	PERB			D30404	PERB		YC056-YR328	
2030B	20	E5	BA	7-4	31-35-05	D30184	32			D00528	5		YL963-YL999, YN236-YR328	
2030R	20	E5	BA	0-0	31-35-05	D30184	33			D00528	4		YL963-YL999, YN236-YR328	
2030Z			BA	0-0	31-35-05	D30184	PERB			D00528	PERB		YL963-YL999, YN236-YR328	
3001B	20	HR	AF	12-2	78-35-21	D30460	18			D30408	2		YC056-YC058	
3001B	20	E6	AF	12-2	78-35-21	D30460	18			D30408	2		YC059-YR328	
3001R	20	HR	AF	0-0	78-35-21	D30460	17			D30408	3		YC056-YC058	
3001R	20	E6	AF	0-0	78-35-21	D30460	17			D30408	3		YC059-YR328	
3001Y	20	HR	AF	0-0	78-35-21	D30460	34			D30408	10		YC056-YC058	
3001Y	20	E6	AF	0-0	78-35-21	D30460	34			D30408	10		YC059-YR328	
3001Z			AF	0-0	78-35-21	D30460	PERB			D30408	PERB		YC056-YR328	
3002B	20	HR	AH	3-5	78-35-21	D30460	41			D30410	2		YC056-YC058	
3002B	20	E6	AH	3-5	78-35-21	D30460	41			D30410	2		YC059-YR328	
3002R	20	HR	AH	0-0	78-35-21	D30460	23			D30410	3		YC056-YC058	
3002R	20	E6	AH	0-0	78-35-21	D30460	23			D30410	3		YC059-YR328	
3002Y	20	HR	AH	0-0	78-35-21	D30460	40			D30410	10		YC056-YC058	
3002Y	20	E6	AH	0-0	78-35-21	D30460	40			D30410	10		YC059-YR328	
3002Z			AH	0-0	78-35-21	D30460	PERB			D30410	PERB		YC056-YR328	
3003B	20	HR	AL	9-1	78-36-21	D30184	19			D30410	5		YC056-YC058	
3003B	20	E6	AL	9-1	78-36-21	D30184	19			D30410	5		YC059-YR328	
3003R	20	HR	AL	0-0	78-36-21	D30184	20			D30410	4		YC056-YC058	
3003R	20	E6	AL	0-0	78-36-21	D30184	20			D30410	4		YC059-YR328	
3003Y	20	HR	AL	0-0	78-36-21	D30184	39			D30410	1		YC056-YC058	
3003Y	20	E6	AL	0-0	78-36-21	D30184	39			D30410	1		YC059-YR328	
3003Z			AL	0-0	78-36-21	D30184	PERB			D30410	PERB		YC056-YR328	
3004B	20	HR	AM	10-11	78-36-21	D30184	38			D30408	5		YC056-YC058	
3004B	20	E6	AM	10-11	78-36-21	D30184	38			D30408	5		YC059-YR328	

WIRE LIST

D280A108

91-21-11

Section W1260

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1268	286A1268			ENGINE STRUT-RIGHT FIREWALL TO AW0258R EEC CH B (continued)											
3004R	20	HR	AM	0-0	78-36-21	D30184		37			D30408		4		YC056-YC058
3004R	20	E6	AM	0-0	78-36-21	D30184		37			D30408		4		YC059-YR328
3004Y	20	HR	AM	0-0	78-36-21	D30184		17			D30408		1		YC056-YC058
3004Y	20	E6	AM	0-0	78-36-21	D30184		17			D30408		1		YC059-YR328
3004Z			AM	0-0	78-36-21	D30184			PERB		D30408		PERB		YC056-YR328
YAAA				0-0	73-21-21	D30184			PERB		OAS0001		PERB		YC056-YR328
YAAB				0-0	36-11-11	D00528			PERB		OAS0004		PERB		YC056-YR328
YAAC				0-0	78-35-21	D30408			PERB		OAS0004		PERB		YC056-YR328
YAAD				0-0	78-36-21	D30410			PERB		OAS0002		PERB		YC056-YR328
YAAE				0-0	30-11-11	D30404			PERB		OAS0003		PERB		YC056-YR328
YAAF				0-0	73-21-21	D30460			PERB		OAS0003		PERB		YC056-YR328
YAAG				0-0	73-21-21	OAS0002			PERB		OAS0003		PERB		YC056-YR328
YAAH				0-0	78-36-21	OAS0001			PERB		OAS0002		PERB		YC056-YR328
YAAJ				0-0	36-11-11	OAS0001			PERB		OAS0004		PERB		YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W1260

Page 7 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To					
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W1270	286A1270			ENGINE STRUT-RIGHT FIREWALL TO AW0258R EEC CH A												
0002	20	HL			2-0	30-21-21	D30428		4		GD03938	DC..	1		ALL	
0009	18	HL			2-0	30-21-21	D30428		11		GD03938	DC..	1		ALL	
0010	18	HL			2-0	30-21-21	D30428		13		GD03938	DC..	1		ALL	
0012	18	HL			2-0	30-21-21	D30428		26		GD03938	DC..	1		ALL	
0015	18	HL			2-0	30-21-21	D30428		28		GD03938	DC..	1		ALL	
1001	20	HP	AB		12-0	74-11-11	D08156P		22		D30412		6		ALL	
1001Z			AB		0-0	74-11-11	D08156P	S/R			D30412	S/R			ALL	
1002	20	HP	AC		3-0	74-11-11	D30412		7		GD03940	AC..	1		ALL	
1002Z			AC		0-0	74-11-11	D30412	S/R			GD03940	ST..	1		ALL	
1003R	20	H9	AD		12-0	26-11-21	D08156P		19		D30452		2		ALL	
1003Z			AD		0-0	26-11-21	D08156P	S/R			D30452	S/R			ALL	
1004R	20	H9	AE		12-0	26-11-21	D08156P		20		D30452		1		ALL	
1004Z			AE		0-0	26-11-21	D08156P	S/R			D30452	S/R			ALL	
1005	20	HP	AG		12-0	73-22-11	D08156P		23		D30412		4		ALL	
1005Z			AG		0-0	73-22-11	D08156P	S/R			D30412	S/R			ALL	
1006	20	HP	AH		3-0	73-22-11	D30412		5		GD03940	AC..	1		ALL	
1006Z			AH		0-0	73-22-11	D30412	S/R			GD03940	ST..	1		ALL	
1007	20	HP	AK		13-0	30-21-21	D08156P		18		D30428		1		ALL	
1007Z			AK		0-0	30-21-21	D08156P	S/R			D30428	S/R			ALL	
1013	20	HP	AR		2-0	30-21-21	D30428		12		SM00001		V1		ALL	
1013Z			AR		0-0	30-21-21	D30428	S/R			SM00001	REF		AA	ALL	
1014	20	HP	AS		2-0	30-21-21	D30428		27		SM00001		V1		ALL	
1014Z			AS		0-0	30-21-21	D30428	S/R			SM00001	REF		AA	ALL	
1016	20	HP	AU		12-0	30-21-21	D08156P		21		SM00001		V1		ALL	
1016Z			AU		0-0	30-21-21	D08156P	S/R			SM00001	REF		AA	ALL	
1017	20	HP	AZ		13-0	31-62-24	D08156P		11		D30428		25		ALL	
1017Z			AZ		0-0	31-62-24	D08156P	S/R			D30428	S/R			ALL	
1018	20	HP	BA		13-0	31-62-24	D30428		29		D08156P		24		ALL	
1018Z			BA		0-0	31-62-24	D30428	S/R			D08156P	S/R			ALL	
2001R	20	RJ	AA		13-0	77-31-21	D08156P		17		D30428		18		ALL	
2001W	20	RJ	AA		0-0	77-31-21	D08156P		6		D30428		19		ALL	
2001Z			AA		0-0	77-31-21	D08156P		7	18	D30428		7		ALL	
2002B	20	HQ	AJ		12-0	77-12-11	D08156P		16		D30412		9		ALL	
2002R	20	HQ	AJ		0-0	77-12-11	D08156P		15		D30412		8		ALL	
2002Z			AJ		0-0	77-12-11	D08156P	S/R			D30412	S/R			ALL	
2003B	20	HQ	AV		13-0	30-21-21	D08156P		9		D30428		24		ALL	
2003R	20	HQ	AV		0-0	30-21-21	D08156P		8		D30428		14		ALL	
2003Z			AV		0-0	30-21-21	D08156P	S/R			D30428	S/R			ALL	
2004B	20	HQ	AW		12-0	SPARE	D08156P		13		D30452		4		ALL	

WIRE LIST

D280A108

91-21-11

Section W1270

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1270	286A1270			ENGINE STRUT-RIGHT FIREWALL TO AW0258R EEC CH A (continued)											
2004R	20	HQ	AW		0-0	SPARE	D08156P	12			D30452	3			ALL
2004Z			AW		0-0	SPARE	D08156P	S/R			D30452	S/R			ALL
2005B	20	HQ	AX		12-0	SPARE	D08156P	14			D30412	2			ALL
2005R	20	HQ	AX		0-0	SPARE	D08156P	4			D30412	1			ALL
2005Z			AX		0-0	SPARE	D08156P	S/R			D30412	S/R			ALL
2006B	20	HQ	AY		13-0	SPARE	D08156P	10			D30428	16			ALL
2006R	20	HQ	AY		0-0	SPARE	D08156P	2			D30428	15			ALL
2006Z			AY		0-0	SPARE	D08156P	S/R			D30428	S/R			ALL
3001B	20	HR	AF		13-0	79-31-11	D08156P	5			D30428	20			ALL
3001R	20	HR	AF		0-0	79-31-11	D08156P	1			D30428	8			ALL
3001Y	20	HR	AF		0-0	79-31-11	D08156P	3			D30428	21			ALL
3001Z			AF		0-0	79-31-11	D08156P	S/R			D30428	S/R			ALL
W1272	286A1272			ENGINE STRUT-RIGHT FIREWALL TO AW0258R EEC CH A											
0003	20	HL			0-7	73-21-11	D30424	13			D30424	28			YC056-YC058
0003	20	GK			0-7	73-21-11	D30424	13			D30424	28			YC059-YR328
2003B	20	HQ	AE		12-6	78-35-21	D30424	41			D30402	9			YC056-YC058
2003B	20	E5	AE		12-6	78-35-21	D30424	41			D30402	9			YC059-YR328
2003R	20	HQ	AE		0-0	78-35-21	D30424	40			D30402	10			YC056-YC058
2003R	20	E5	AE		0-0	78-35-21	D30424	40			D30402	10			YC059-YR328
2003Z			AE		0-0	78-35-21	D30424	PERB			D30402	PERB			YC056-YR328
2004B	20	HQ	AG		4-4	78-35-21	D30424	38			D30406	9			YC056-YC058
2004B	20	E5	AG		4-4	78-35-21	D30424	38			D30406	9			YC059-YR328
2004R	20	HQ	AG		0-0	78-35-21	D30424	39			D30406	10			YC056-YC058
2004R	20	E5	AG		0-0	78-35-21	D30424	39			D30406	10			YC059-YR328
2004Z			AG		0-0	78-35-21	D30424	PERB			D30406	PERB			YC056-YR328
2007B	20	HQ	AN		10-9	73-21-11	D30142	23			D30424	3			YC056-YC058
2007B	20	E5	AN		10-9	73-21-11	D30142	23			D30424	3			YC059-YR328
2007R	20	HQ	AN		0-0	73-21-11	D30142	22			D30424	2			YC056-YC058
2007R	20	E5	AN		0-0	73-21-11	D30142	22			D30424	2			YC059-YR328
2007Z			AN		0-0	73-21-11	D30142	PERB			D30424	PERB			YC056-YR328
2008B	20	HQ	AS		10-9	73-21-12	D30142	31			D30424	37			YC056-YC058
2008B	20	E5	AS		10-9	73-21-12	D30142	31			D30424	37			YC059-YR328
2008R	20	HQ	AS		0-0	73-21-12	D30142	30			D30424	20			YC056-YC058
2008R	20	E5	AS		0-0	73-21-12	D30142	30			D30424	20			YC059-YR328
2008Z			AS		0-0	73-21-12	D30142	PERB			D30424	PERB			YC056-YR328
2009B	20	HQ	AT		10-9	73-21-21	D30142	11			D30424	33			YC056-YC058
2009B	20	E5	AT		10-9	73-21-21	D30142	11			D30424	33			YC059-YR328
2009R	20	HQ	AT		0-0	73-21-21	D30142	26			D30424	17			YC056-YC058

WIRE LIST

D280A108

91-21-11

Section W1270

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From			To			Effectivity		
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W1272	286A1272			ENGINE STRUT-RIGHT FIREWALL TO AW0258R EEC CH A (continued)											
2009R	20	E5	AT		0-0	73-21-21	D30142		26		D30424		17	YC059-YR328	
2009Z			AT		0-0	73-21-21	D30142		PERB		D30424		PERB	YC056-YR328	
2010B	20	HQ	AU		10-9	73-21-21	D30142		27		D30424		34	YC056-YC058	
2010B	20	E5	AU		10-9	73-21-21	D30142		27		D30424		34	YC059-YR328	
2010R	20	HQ	AU		0-0	73-21-21	D30142		28		D30424		18	YC056-YC058	
2010R	20	E5	AU		0-0	73-21-21	D30142		28		D30424		18	YC059-YR328	
2010Z			AU		0-0	73-21-21	D30142		PERB		D30424		PERB	YC056-YR328	
2011B	20	HQ	AV		10-9	73-21-21	D30142		25		D30424		7	YC056-YC058	
2011B	20	E5	AV		10-9	73-21-21	D30142		25		D30424		7	YC059-YR328	
2011R	20	HQ	AV		0-0	73-21-21	D30142		24		D30424		6	YC056-YC058	
2011R	20	E5	AV		0-0	73-21-21	D30142		24		D30424		6	YC059-YR328	
2011Z			AV		0-0	73-21-21	D30142		PERB		D30424		PERB	YC056-YR328	
2012B	20	HQ	AW		10-9	73-24-21	D30142		34		D30424		4	YC056-YC058	
2012B	20	E5	AW		10-9	73-24-21	D30142		34		D30424		4	YC059-YR328	
2012R	20	HQ	AW		0-0	73-24-21	D30142		33		D30424		1	YC056-YC058	
2012R	20	E5	AW		0-0	73-24-21	D30142		33		D30424		1	YC059-YR328	
2012Z			AW		0-0	73-24-21	D30142		PERB		D30424		PERB	YC056-YR328	
2013B	20	HQ	AX		10-9	73-24-12	D30142		35		D30424		14	YC056-YC058	
2013B	20	E5	AX		10-9	73-24-12	D30142		35		D30424		14	YC059-YR328	
2013R	20	HQ	AX		0-0	73-24-12	D30142		15		D30424		5	YC056-YC058	
2013R	20	E5	AX		0-0	73-24-12	D30142		15		D30424		5	YC059-YR328	
2013Z			AX		0-0	73-24-12	D30142		PERB		D30424		PERB	YC056-YR328	
2014B	20	HQ	AY		10-8	SPARE	D30142		12		D30402		11	YC056-YC058	
2014B	20	E5	AY		10-8	SPARE	D30142		12		D30402		11	YC059-YR328	
2014R	20	HQ	AY		0-0	SPARE	D30142		3		D30402		2	YC056-YC058	
2014R	20	E5	AY		0-0	SPARE	D30142		3		D30402		2	YC059-YR328	
2014Z			AY		0-0	SPARE	D30142		PERB		D30402		PERB	YC056-YR328	
2016B	20	HQ	BA		9-0	SPARE	D30142		14		D30406		11	YC056-YC058	
2016B	20	E5	BA		9-0	SPARE	D30142		14		D30406		11	YC059-YR328	
2016R	20	HQ	BA		0-0	SPARE	D30142		32		D30406		2	YC056-YC058	
2016R	20	E5	BA		0-0	SPARE	D30142		32		D30406		2	YC059-YR328	
2016Z			BA		0-0	SPARE	D30142		PERB		D30406		PERB	YC056-YR328	
2017B	20	HQ	BD		10-9	74-31-11	D30424		23		D30142		29	YC056-YC058	
2017B	20	E5	BD		10-9	74-31-11	D30424		23		D30142		29	YC059-YR328	
2017R	20	HQ	BD		0-0	74-31-11	D30424		22		D30142		13	YC056-YC058	
2017R	20	E5	BD		0-0	74-31-11	D30424		22		D30142		13	YC059-YR328	
2017Z			BD		0-0	74-31-11	D30424		PERB		D30142		PERB	YC056-YR328	
2022B	20	HQ	AC		10-9	78-35-21	D30142		36		D30424		10	YC056-YC058	
2022B	20	E5	AC		10-9	78-35-21	D30142		36		D30424		10	YC059-YR328	

WIRE LIST

D280A108

91-21-11

Section W1270

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1272	286A1272			ENGINE STRUT-RIGHT FIREWALL TO AW0258R EEC CH A (continued)											
2022R	20	HQ	AC		0-0	78-35-21	D30142		37		D30424		9		YC056-YC058
2022R	20	E5	AC		0-0	78-35-21	D30142		37		D30424		9		YC059-YR328
2022Z			AC		0-0	78-35-21	D30142		PERB		D30424		PERB		YC056-YR328
2023B	20	HQ	AQ		10-9	73-21-12	D30424		30		D30142		9		YC056-YC058
2023B	20	E5	AQ		10-9	73-21-12	D30424		30		D30142		9		YC059-YR328
2023R	20	HQ	AQ		0-0	73-21-12	D30424		15		D30142		21		YC056-YC058
2023R	20	E5	AQ		0-0	73-21-12	D30424		15		D30142		21		YC059-YR328
2023Z			AQ		0-0	73-21-12	D30424		PERB		D30142		PERB		YC056-YR328
3001B	20	HR	AF		12-6	78-35-21	D30424		35		D30402		5		YC056-YC058
3001B	20	E6	AF		12-6	78-35-21	D30424		35		D30402		5		YC059-YR328
3001R	20	HR	AF		0-0	78-35-21	D30424		19		D30402		6		YC056-YC058
3001R	20	E6	AF		0-0	78-35-21	D30424		19		D30402		6		YC059-YR328
3001Y	20	HR	AF		0-0	78-35-21	D30424		36		D30402		4		YC056-YC058
3001Y	20	E6	AF		0-0	78-35-21	D30424		36		D30402		4		YC059-YR328
3001Z			AF		0-0	78-35-21	D30424		PERB		D30402		PERB		YC056-YR328
3002B	20	HR	AH		4-4	78-35-21	D30424		16		D30406		5		YC056-YC058
3002B	20	E6	AH		4-4	78-35-21	D30424		16		D30406		5		YC059-YR328
3002R	20	HR	AH		0-0	78-35-21	D30424		31		D30406		6		YC056-YC058
3002R	20	E6	AH		0-0	78-35-21	D30424		31		D30406		6		YC059-YR328
3002Y	20	HR	AH		0-0	78-35-21	D30424		32		D30406		4		YC056-YC058
3002Y	20	E6	AH		0-0	78-35-21	D30424		32		D30406		4		YC059-YR328
3002Z			AH		0-0	78-35-21	D30424		PERB		D30406		PERB		YC056-YR328
3003B	18	HR	AB		10-8	78-32-61	D30142		7		D30402		12		YC056-YC058
3003B	18	E6	AB		10-8	78-32-61	D30142		7		D30402		12		YC059-YR328
3003R	18	HR	AB		0-0	78-32-61	D30142		17		D30402		3		YC056-YC058
3003R	18	E6	AB		0-0	78-32-61	D30142		17		D30402		3		YC059-YR328
3003Y	18	HR	AB		0-0	78-32-61	D30142		1		D30402		13		YC056-YC058
3003Y	18	E6	AB		0-0	78-32-61	D30142		1		D30402		13		YC059-YR328
3003Z			AB		0-0	78-32-61	D30142		PERB		D30402		PERB		YC056-YR328
3004B	18	HR	AA		9-0	78-32-61	D30142		16		D30406		12		YC056-YC058
3004B	18	E6	AA		9-0	78-32-61	D30142		16		D30406		12		YC059-YR328
3004R	18	HR	AA		0-0	78-32-61	D30142		6		D30406		3		YC056-YC058
3004R	18	E6	AA		0-0	78-32-61	D30142		6		D30406		3		YC059-YR328
3004Y	18	HR	AA		0-0	78-32-61	D30142		5		D30406		13		YC056-YC058
3004Y	18	E6	AA		0-0	78-32-61	D30142		5		D30406		13		YC059-YR328
3004Z			AA		0-0	78-32-61	D30142		PERB		D30406		PERB		YC056-YR328
3005B	20	HR	AL		9-0	78-36-21	D30142		19		D30406		8		YC056-YC058
3005B	20	E6	AL		9-0	78-36-21	D30142		19		D30406		8		YC059-YR328
3005R	20	HR	AL		0-0	78-36-21	D30142		20		D30406		7		YC056-YC058

WIRE LIST

D280A108

91-21-11

Section W1270

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Diagram	From	To									
	Wire No.	GA	CO TY			Fam	FT-IN	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1272	286A1272			ENGINE STRUT-RIGHT FIREWALL TO AW0258R EEC CH A (continued)												
3005R	20	E6	AL		0-0	78-36-21	D30142		20			D30406	7			YC059-YR328
3005Y	20	HR	AL		0-0	78-36-21	D30142		8			D30406	1			YC056-YC058
3005Y	20	E6	AL		0-0	78-36-21	D30142		8			D30406	1			YC059-YR328
3005Z			AL		0-0	78-36-21	D30142	PERB				D30406	PERB			YC056-YR328
3006B	20	HR	AM		10-8	78-36-21	D30142		38			D30402	8			YC056-YC058
3006B	20	E6	AM		10-8	78-36-21	D30142		38			D30402	8			YC059-YR328
3006R	20	HR	AM		0-0	78-36-21	D30142		39			D30402	7			YC056-YC058
3006R	20	E6	AM		0-0	78-36-21	D30142		39			D30402	7			YC059-YR328
3006Y	20	HR	AM		0-0	78-36-21	D30142		18			D30402	1			YC056-YC058
3006Y	20	E6	AM		0-0	78-36-21	D30142		18			D30402	1			YC059-YR328
3006Z			AM		0-0	78-36-21	D30142	PERB				D30402	PERB			YC056-YR328
YAAA					0-0	78-35-21	D30424	PERB				OAS0001	PERB			YC056-YR328
YAAB					0-0	78-36-21	D30406	PERB				OAS0001	PERB			YC056-YR328
YAAC					0-0	78-32-51	D30142	PERB				OAS0002	PERB			YC056-YR328
YAAD					0-0	78-36-21	D30402	PERB				OAS0002	PERB			YC056-YR328
YAAE					0-0	78-36-21	OAS0001	PERB				OAS0002	PERB			YC056-YR328
W1278	286A1278			LEADING EDGE-RIGHT WING EEC CH A												
1001	20	HW	AA		14-6	73-22-11	D39928		5			D08156J	23			ALL
1001Z			AA		0-0	73-22-11	D39928	S/R				D08156J	S/R			ALL
1002	20	HW	AB		14-6	74-11-11	D39928		3			D08156J	22			ALL
1002Z			AB		0-0	74-11-11	D39928	S/R				D08156J	S/R			ALL
1003	20	HP	AC		14-6	30-21-21	D39928		38			D08156J	18			ALL
1003Z			AC		0-0	30-21-21	D39928	S/R				D08156J	S/R			ALL
1004	20	HP	AD		14-6	30-21-21	D39928		21			D08156J	8			ALL
1004Z			AD		0-0	30-21-21	D39928	S/R				D08156J	S/R			ALL
1005	20	HP	AE		14-6	30-21-21	D39928		22			D08156J	9			ALL
1005Z			AE		0-0	30-21-21	D39928	S/R				D08156J	S/R			ALL
1006	20	HP	AF		14-6	30-21-21	D39928		23			D08156J	21			ALL
1006Z			AF		0-0	30-21-21	D39928	S/R				D08156J	S/R			ALL
1007R	20	H9	AG		14-6	26-11-21	D39928		28			D08156J	19			ALL
1007Z			AG		0-0	26-11-21	D39928	S/R				D08156J	S/R			ALL
1008R	20	H9	AH		14-6	26-11-21	D39928		29			D08156J	20			ALL
1008Z			AH		0-0	26-11-21	D39928	S/R				D08156J	S/R			ALL
1009	20	HP	AQ		20-4	28-21-11	D00790		2			D39928	30			ALL
1009Z			AQ		0-0	28-21-11	D00790	S/R				D39928	S/R			ALL
1010	20	HP	AR		20-4	28-21-11	D00790		3			D39928	32			ALL
1010Z			AR		0-0	28-21-11	D00790	S/R				D39928	S/R			ALL
1011	18	HE	AS		1-9	28-21-11	D00790		4			GD03984	DC..	E	*	ALL

WIRE LIST

D280A108

91-21-11

Section W1270

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1278	286A1278			LEADING EDGE-RIGHT WING EEC CH A (continued)											
1011Z				AS	0-0	28-21-11	D00790		S/R		GD03984	DC..	E	*	ALL
1012	20	HP		AT	20-4	28-21-11	D00790		5		D39928	31			ALL
1012Z				AT	0-0	28-21-11	D00790		S/R		D39928	S/R			ALL
1013	18	HP		AU	1-10	28-21-11	D00790		7		GD03986	ST..	E	*	ALL
1013Z				AU	0-0	28-21-11	D00790		S/R		GD03986	ST..	E	*	ALL
1014	20	HP		AV	14-6	31-62-24	D39928		8		D08156J	11			ALL
1014Z				AV	0-0	31-62-24	D39928		S/R		D08156J	S/R			ALL
1015	20	HP		BA	14-6	31-62-24	D08156J		24		D39928	33			ALL
1015Z				BA	0-0	31-62-24	D08156J		S/R		D39928	S/R			ALL
2001B	20	HQ		AJ	14-6	SPARE	D39928		11		D08156J	13			ALL
2001R	20	HQ		AJ	0-0	SPARE	D39928		24		D08156J	12			ALL
2001Z				AJ	0-0	SPARE	D39928		S/R		D08156J	S/R			ALL
2002B	20	HQ		AK	14-6	SPARE	D39928		10		D08156J	10			ALL
2002R	20	HQ		AK	0-0	SPARE	D39928		2		D08156J	2			ALL
2002Z				AK	0-0	SPARE	D39928		S/R		D08156J	S/R			ALL
2003B	20	HQ		AL	14-6	SPARE	D39928		15		D08156J	14			ALL
2003R	20	HQ		AL	0-0	SPARE	D39928		16		D08156J	4			ALL
2003Z				AL	0-0	SPARE	D39928		S/R		D08156J	S/R			ALL
2004B	20	HX		AM	14-6	77-12-11	D39928		39		D08156J	16			ALL
2004R	20	HX		AM	0-0	77-12-11	D39928		19		D08156J	15			ALL
2004Z				AM	0-0	77-12-11	D39928		S/R		D08156J	S/R			ALL
2005R	20	RQ		AN	14-6	77-31-21	D39928		17		D08156J	17			YC051-YD153
2005R	20	RQ		AN	14-6	77-31-21	D39928		6		D08156J	17			YD154-YR328
2005W	20	RQ		AN	0-0	77-31-21	D39928		18		D08156J	6			YC051-YD153
2005W	20	RQ		AN	0-0	77-31-21	D39928		1		D08156J	6			YD154-YR328
2005ZI				AN	0-0	77-31-21	D39928		7		D08156J	7			ALL
2005ZO				AN	0-0	77-31-21	D39928		S/R		D08156J	S/R			ALL
3001B	20	HR		AP	14-6	79-31-11	D39928		36		D08156J	5			ALL
3001R	20	HR		AP	0-0	79-31-11	D39928		35		D08156J	1			ALL
3001Y	20	HR		AP	0-0	79-31-11	D39928		37		D08156J	3			ALL
3001Z				AP	0-0	79-31-11	D39928		S/R		D08156J	S/R			ALL

WIRE LIST

D280A108

91-21-11
Section W1270
Page 6 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W1280	286A1280				RIGHTWING/BODY PRESSURE SEAL TO FRONT SPAR INBOARD										
2001B	20	HQ	AP		10-4	27-81-21	D39940	29			SP00492		9		YC051-YN236, YN501-YR314
2001B	20	HQ	AP		10-5	27-81-21	D39940	29			SP00492		9		YR315-YR328
2001R	20	HQ	AP		0-0	27-81-21	D39940	13			SP00560		9		YC051-YN236, YN501-YR328
2001Z			AP		0-0	27-81-21	D39940	S/R			GD04228	ST..	E		YC051-YN236, YN501-YR328
2002B	20	HQ	AQ		10-9	27-81-21	D39940	30			SP00490		9		YC051-YN236, YN501-YR314
2002B	20	HQ	AQ		10-11	27-81-21	D39940	30			SP00490		9		YR315-YR328
2002R	20	HQ	AQ		0-0	27-81-21	D39940	31			SP00558		9		YC051-YN236, YN501-YR328
2002Z			AQ		0-0	27-81-21	D39940	S/R			GD04230	ST..	E		YC051-YN236, YN501-YR328
2003B	20	HQ	AR		9-3	27-81-21	D39940	32			SP00486		9		YC051-YN236, YN501-YR314
2003B	20	HQ	AR		9-4	27-81-21	D39940	32			SP00486		9		YR315-YR328
2003R	20	HQ	AR		0-0	27-81-21	D39940	33			SP00554		9		YC051-YN236, YN501-YR328
2003Z			AR		0-0	27-81-21	D39940	S/R			GD04226	ST..	GW		YC051-YN236, YN501-YR328
2004B	20	HQ	AS		9-3	27-81-21	D39940	35			SP00488		9		YC051-YN236, YN501-YR314
2004B	20	HQ	AS		9-4	27-81-21	D39940	35			SP00488		9		YR315-YR328
2004R	20	HQ	AS		0-0	27-81-21	D39940	34			SP00556		9		YC051-YN236, YN501-YR328
2004Z			AS		0-0	27-81-21	D39940	S/R			GD04226	ST..	GW		YC051-YN236, YN501-YR328
3001B	18	HR	AA		4-10	28-23-11	D39940	1			D00076		3		YC051-YC064
3001B	18	HR	AA		5-3	28-23-11	D39940	1			D00076		3		YC065-YN236, YN501-YR328
3001R	18	HR	AA		0-0	28-23-11	D39940	3			D00076		1		YC051-YD153
3001R	18	HR	AA		0-0	28-23-11	D39940	9			D00076		1		YD154-YN236, YN501-YR328
3001Y	18	HR	AA		0-0	28-23-11	D39940	5			D00076		2		YC051-YD153
3001Y	18	HR	AA		0-0	28-23-11	D39940	17			D00076		2		YD154-YN236, YN501-YR328
3001Z			AA		0-0	28-23-11	D39940	S/R			D00076			AA	YC051-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W1280

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Fam	Description FT-IN Diagram		From Equip Term Type Splice			To Equip Term Type Splice Effectivity					
W1280	286A1280				RIGHTWING/BODY PRESSURE SEAL TO FRONT SPAR INBOARD (continued)										
6001	18		HL		3-2	28-23-11	D00076			AA	GD00262	ST..	GW		YC051-YC064
6001	18		HL		2-5	28-23-11	D00076			AA	GD00262	ST..	GW		YC065-YN236, YN501-YR314
6001	18		HL		2-7	28-23-11	D00076			AA	GD00262	ST..	GW		YR315-YR328
I-B					0-0	27-81-21	S00175		BLU		SP00492		9		YC051-YN236, YN501-YR328
I-R					0-0	27-81-21	S00175		RED		SP00560		9		YC051-YN236, YN501-YR328
I-Y					0-0	27-81-21	S00175		YEL		GD04094	AC..	E		YC051-YN236, YN501-YR328
J-B					0-0	27-81-21	S00174		BLU		SP00490		9		YC051-YN236, YN501-YR328
J-R					0-0	27-81-21	S00174		RED		SP00558		9		YC051-YN236, YN501-YR328
J-Y					0-0	27-81-21	S00174		YEL		GD00144	AC..	E		YC051-YN236, YN501-YR328
K-B					0-0	27-81-21	S00172		BLU		SP00486		9		YC051-YN236, YN501-YR328
K-R					0-0	27-81-21	S00172		RED		SP00554		9		YC051-YN236, YN501-YR328
K-Y					0-0	27-81-21	S00172		YEL		GD00148	AC..	E		YC051-YN236, YN501-YR328
L-B					0-0	27-81-21	S00173		BLU		SP00488		9		YC051-YN236, YN501-YR328
L-R					0-0	27-81-21	S00173		RED		SP00556		9		YC051-YN236, YN501-YR328
L-Y					0-0	27-81-21	S00173		YEL		GD00148	AC..	E		YC051-YN236, YN501-YR328
W1282	286A1282				LEADING EDGE-RIGHT WING EEC CH B										
1001R	20		H9	AC	15-0	26-11-21	D39932		9		D30162		5		ALL
1001Z				AC	0-0	26-11-21	D39932		S/R		D30162		S/R		ALL
1002R	20		H9	AD	15-0	26-11-21	D39932		10		D30162		4		ALL
1002Z				AD	0-0	26-11-21	D39932		S/R		D30162		S/R		ALL
1003R	18		H9	AE	12-0	26-12-11	M01764		=B	E	D30162		6	18	ALL
1003Z				AE	0-0	26-12-11	GD04024		ST..	E	D30162		S/R		ALL
1004	20		HW	AJ	15-0	73-22-11	D39932		7		D30162		21		ALL
1004Z				AJ	0-0	73-22-11	D39932		S/R		D30162		S/R		ALL
1005R	20		H9	AG	2-2	26-12-11	D30162		8		D00838		=1		ALL

WIRE LIST

D280A108

91-21-11

Section W1280

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1282		286A1282			LEADING EDGE-RIGHT WING EEC CH B (continued)											
1005Z					AG	0-0	26-12-11	D30162		S/R		D00838		DED		ALL
1007		20		HW	AH	15-0	74-11-11	D39932		11		D30162		14		YC051-YD153
1007		20		HW	AH	15-0	74-11-11	D39932		6		D30162		14		YD154-YR328
1007Z					AH	0-0	74-11-11	D39932		S/R		D30162		S/R		ALL
2001B		20		HQ	AA	15-0	SPARE	D39932		2		D30162		16		ALL
2001R		20		HQ	AA	0-0	SPARE	D39932		3		D30162		15		ALL
2001Z					AA	0-0	SPARE	D39932		S/R		D30162		S/R		ALL
2002B		20		HQ	AB	15-0	SPARE	D39932		4		D30162		18		ALL
2002R		20		HQ	AB	0-0	SPARE	D39932		5		D30162		17		ALL
2002Z					AB	0-0	SPARE	D39932		S/R		D30162		S/R		ALL
W1284		286A1284			LEADING EDGE-RIGHT WING IDG CONTROLS											
1001		20		HP	AA	13-8	29-11-11	D39936		30		D30114		25		YC051-YD153
1001		20		HP	AA	13-8	29-11-11	D39936		18		D30114		25		YD154-YR328
1001Z					AA	0-0	29-11-11	D39936		S/R		D30114		S/R		ALL
1002		18		HP	AB	13-8	24-11-21	D30114		17		D39936		10		YC051-YD158
1002		18		HP	AB	13-10	24-11-21	D30114		7		D39936		10		YD160-YL999, YN232-YR328
1002		18		HP	AB	13-10	24-11-21	D30114		17		D39936		10		YN231
1002Z					AB	0-0	24-11-21	D30114		S/R		D39936		S/R		ALL
1003		20		HP	AC	14-7	80-11-11	D39912		11		D30114		18		YC051-YD158, YN231
1003		20		HP	AC	14-9	80-11-11	D39912		11		D30114		18		YD160-YL999, YN232-YR328
1003Z					AC	0-0	80-11-11	D39912		S/R		D30114		S/R		ALL
1004		20		HP	AD	14-7	76-21-21	D39912		10		D30114		39		YC051-YD158, YN231
1004		20		HP	AD	14-9	76-21-21	D39912		10		D30114		39		YD160-YL999, YN232-YR328
1004Z					AD	0-0	76-21-21	D39912		S/R		D30114		S/R		ALL
1005		20		HP	AE	14-7	80-11-11	D39912		7		D30114		38		YC051-YD158, YN231
1005		20		HP	AE	14-9	80-11-11	D39912		7		D30114		38		YD160-YL999, YN232-YR328
1005Z					AE	0-0	80-11-11	D39912		S/R		D30114		S/R		ALL
2001B		20		HQ	AF	13-8	SPARE	D39936		26		D30114		21		YC051-YD158
2001B		20		HQ	AF	13-10	SPARE	D39936		26		D30114		30		YD160-YL999, YN232-YR328
2001B		20		HQ	AF	13-10	SPARE	D39936		26		D30114		21		YN231
2001R		20		HQ	AF	0-0	SPARE	D39936		25		D30114		20		YC051-YD158, YN231
2001R		20		HQ	AF	0-0	SPARE	D39936		25		D30114		32		YD160-YL999, YN232-YR328

WIRE LIST

D280A108

91-21-11

Section W1280

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1284	286A1284			LEADING EDGE-RIGHT WING IDG CONTROLS (continued)											
2001Z				AF	0-0	SPARE	D39936	S/R			D30114	S/R			ALL
2002B	20	HQ	AG		13-8	24-11-21	D30114	2			D39936	39			YC051-YD158
2002B	20	HQ	AG		13-10	24-11-21	D30114	9			D39936	39			YD160-YL999, YN232-YR328
2002B	20	HQ	AG		13-10	24-11-21	D30114	2			D39936	39			YN231
2002R	20	HQ	AG		0-0	24-11-21	D30114	10			D39936	19			ALL
2002Z			AG		0-0	24-11-21	D30114	S/R			D39936	S/R			ALL
2003B	20	HX	AH		14-7	77-12-21	D39912	3			D30114	29			YC051-YD158, YN231
2003B	20	HX	AH		14-9	77-12-21	D39912	3			D30114	29			YD160-YL999, YN232-YR328
2003R	20	HX	AH		0-0	77-12-21	D39912	4			D30114	30			YC051-YD158, YN231
2003R	20	HX	AH		0-0	77-12-21	D39912	4			D30114	21			YD160-YL999, YN232-YR328
2003Z			AH		0-0	77-12-21	D39912	S/R			D30114	S/R			ALL
2004B	20	HQ	AJ		14-7	SPARE	D39912	6			D30114	37			YC051-YD158, YN231
2004B	20	HQ	AJ		14-9	SPARE	D39912	6			D30114	37			YD160-YL999, YN232-YR328
2004R	20	HQ	AJ		0-0	SPARE	D39912	5			D30114	36			ALL
2004Z			AJ		0-0	SPARE	D39912	S/R			D30114	S/R			ALL
2005B	20	HX	AK		14-7	76-21-21	D39912	8			D30114	19			YC051-YD158, YN231
2005B	20	HX	AK		14-9	76-21-21	D39912	8			D30114	19			YD160-YL999, YN232-YR328
2005R	20	HX	AK		0-0	76-21-21	D39912	9			D30114	8			ALL
2005Z			AK		0-0	76-21-21	D39912	S/R			D30114	S/R			ALL
2006B	20	M2	AM		13-8	24-21-21	D30114	4			D39936	38			YC051-YD158
2006B	20	M2	AM		13-10	24-21-21	D30114	24			D39936	38			YD160-YL999, YN232-YR328
2006B	20	M2	AM		13-10	24-21-21	D30114	4			D39936	38			YN231
2006R	20	M2	AM		0-0	24-21-21	D30114	1			D39936	37			ALL
2006ZI			AM		0-0	24-21-21	D30114	11	18		D39936	36	18		ALL
2006ZO			AM		0-0	24-21-21	D30114	S/R			D39936	S/R			ALL
3001B	18	M3	AN		13-8	24-21-21	D30114	14			D39936	17			YC051-YD153
3001B	18	M3	AN		13-8	24-21-21	D30114	14			D39936	12			YD154-YD158
3001B	18	M3	AN		13-10	24-21-21	D30114	14			D39936	12			YD160-YR328
3001R	18	M3	AN		0-0	24-21-21	D30114	12			D39936	6			YC051-YD153
3001R	18	M3	AN		0-0	24-21-21	D30114	12			D39936	1			YD154-YR328
3001Y	18	M3	AN		0-0	24-21-21	D30114	5			D39936	16			YC051-YD153
3001Y	18	M3	AN		0-0	24-21-21	D30114	5			D39936	14			YD154-YD158, YN231

WIRE LIST

D280A108

91-21-11

Section W1280

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To			Effectivity					
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type		Splice	Equip	Term	Type	Splice
W1284	286A1284			LEADING EDGE-RIGHT WING IDG CONTROLS (continued)												
3001Y	18	M3	AN		0-0	24-21-21	D30114		16			D39936	14			YD160-YL999, YN232-YR328
3001ZI			AN		0-0	24-21-21	D30114		13	18		D39936	5			YC051-YD158, YN231
3001ZI			AN		0-0	24-21-21	D30114		23	18		D39936	5			YD160-YL999, YN232-YR328
3001ZO			AN		0-0	24-21-21	D30114		S/R			D39936	S/R			ALL
4001B	20	HS	AL		13-8	24-24-21	D30114		33			D39936	33			YC051-YD153
4001B	20	HS	AL		13-8	24-24-21	D30114		33			D39936	15			YD154-YD158
4001B	20	HS	AL		13-10	24-24-21	D30114		33			D39936	15			YD160-YR328
4001G	20	HS	AL		0-0	24-24-21	D30114		15			D39936	15			YC051-YD153
4001G	20	HS	AL		0-0	24-24-21	D30114		15			D39936	33			YD154-YD158, YN231
4001G	20	HS	AL		0-0	24-24-21	D30114		22			D39936	33			YD160-YL999, YN232-YR328
4001R	20	HS	AL		0-0	24-24-21	D30114		31			D39936	34			YC051-YD153
4001R	20	HS	AL		0-0	24-24-21	D30114		31			D39936	35			YD154-YD158, YN231
4001R	20	HS	AL		0-0	24-24-21	D30114		34			D39936	35			YD160-YL999, YN232-YR328
4001Y	20	HS	AL		0-0	24-24-21	D30114		32			D39936	35			YC051-YD153
4001Y	20	HS	AL		0-0	24-24-21	D30114		32			D39936	32			YD154-YD158, YN231
4001Y	20	HS	AL		0-0	24-24-21	D30114		20			D39936	32			YD160-YL999, YN232-YR328
4001Z			AL		0-0	24-24-21	D30114		S/R			D39936	S/R			ALL
W1286	286A1286			LEADING EDGE-RIGHT WING POWER FEEDERS												
0001	02	HA			2-5	24-21-21	D08194J		A			SM00001		GX		ALL
0002	02	HA			2-5	24-21-21	D08194J		B			SM00002		GX		YC051-YC059
0002	02	HA			2-4	24-21-21	D08194J		B			SM00002		GX		YC060-YR328
0003	02	HA			2-7	24-21-21	D08194J		C			SM00003		GX		ALL
0004	04	HA			2-6	24-21-21	D08194J		D			GD03934	AC..	IA		ALL
0005	*1	QY			48-2	24-21-21	TB5005		A	H1		SM00001		GX		YC051-YL964
0005	*1	QY			48-1	24-21-21	TB5005		A	H1		SM00001		GX		YL965-YL999, YR301-YR328
0005	*1	QY			38-3	24-21-21	TB5005		A	H1		SM00001		GX		YN231-YN235
0005	*1	QY			38-5	24-21-21	TB5005		A	H1		SM00001		GX		YN236-YN501
0006	*1	QY			48-2	24-21-21	TB5005		B	H1		SM00002		GX		YC051-YL964
0006	*1	QY			48-5	24-21-21	TB5005		B	H1		SM00002		GX		YL965-YL999, YR301-YR328
0006	*1	QY			38-3	24-21-21	TB5005		B	H1		SM00002		GX		YN231-YN235
0006	*1	QY			38-8	24-21-21	TB5005		B	H1		SM00002		GX		YN236-YN501

WIRE LIST

D280A108

91-21-11

Section W1280

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W1286	286A1286				LEADING EDGE-RIGHT WING POWER FEEDERS (continued)												
0007	*1	QY			48-4	24-21-21		TB5005	C	H1		SM00003		GX		YC051-YL964	
0007	*1	QY			48-11	24-21-21		TB5005	C	H1		SM00003		GX		YL965-YL999, YR301-YR328	
0007	*1	QY			38-3	24-21-21		TB5005	C	H1		SM00003		GX		YN231-YN235	
0007	*1	QY			39-3	24-21-21		TB5005	C	H1		SM00003		GX		YN236-YN501	
W1288	286A1288				RIGHT WING BODY PRESSURE SEAL TO FRONT SPAR OUTBD												
1012	20	HP	AM		20-9	30-11-11		D39904	10			D00736	1			YC051-YD153	
1012	20	HP	AM		20-9	30-11-11		D39904	2			D00736	1			YD154-YD158	
1012	20	HP	AM		20-10	30-11-11		D39904	2			D00736	1			YD160-YR328	
1012Z			AM		0-0	30-11-11		D39904	S/R			D00736	S/R			ALL	
1013	20	HP	AN		1-8	30-11-11		D00736	2			GD03984	DC..	E	*1	YC051-YD158	
1013	20	HP	AN		2-3	30-11-11		D00736	2			GD03984	DC..	E	*1	YD160-YR328	
1013Z			AN		0-0	30-11-11		D00736	S/R			GD03984	DC..	E	*1	ALL	
1014R	18	H9	BB		19-7	26-12-11		D39904	14			M01764	=A	E		YC051-YD153	
1014R	18	H9	BB		19-7	26-12-11		D39904	1			M01764	=A	E		YD154-YD158	
1014R	18	H9	BB		19-9	26-12-11		D39904	1			M01764	=A	E		YD160-YR328	
1014Z			BB		0-0	26-12-11		D39904	S/R			GD04024	ST..	E		ALL	
2005B	20	HQ	AT		26-11	27-81-22		D39904	36			SP03440		9		YC051-YD158	
2005B	20	HQ	AT		27-0	27-81-22		D39904	36			SP03440		9		YD160-YR328	
2005R	20	HQ	AT		0-0	27-81-22		D39904	35			SP03438		9		ALL	
2005Z			AT		0-0	27-81-22		D39904	S/R			GD04096	ST..	E		ALL	
2006B	20	HQ	AU		23-7	27-81-22		D39904	28			SP03446		9		ALL	
2006R	20	HQ	AU		0-0	27-81-22		D39904	27			SP03442		9		ALL	
2006Z			AU		0-0	27-81-22		D39904	S/R			GD04098	ST..	E		ALL	
2007B	20	HQ	AV		37-4	27-81-22		D39904	38			SP03450		9		YC051-YD158	
2007B	20	HQ	AV		37-3	27-81-22		D39904	38			SP03450		9		YD160-YR328	
2007R	20	HQ	AV		0-0	27-81-22		D39904	37			SP03448		9		ALL	
2007Z			AV		0-0	27-81-22		D39904	S/R			GD04090	ST..	E		ALL	
2008B	20	HQ	AW		33-9	27-81-22		D39904	18			SP03456		9		YC051-YD158	
2008B	20	HQ	AW		33-8	27-81-22		D39904	18			SP03456		9		YD160-YR328	
2008R	20	HQ	AW		0-0	27-81-22		D39904	39			SP03454		9		ALL	
2008Z			AW		0-0	27-81-22		D39904	S/R			GD04092	ST..	E		ALL	
2009B	20	HQ	AX		48-8	27-81-22		D39904	19			SP03460		9		ALL	
2009R	20	HQ	AX		0-0	27-81-22		D39904	8			SP03458		9		ALL	
2009Z			AX		0-0	27-81-22		D39904	S/R			GD04300	ST..	E		ALL	
2010B	20	HQ	AY		44-10	27-81-22		D39904	21			SP03466		9		ALL	
2010R	20	HQ	AY		0-0	27-81-22		D39904	20			SP03462		9		ALL	
2010Z			AY		0-0	27-81-22		D39904	S/R			GD04302	ST..	E		ALL	

WIRE LIST

D280A108

91-21-11

Section W1280

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1288	286A1288			RIGHT WING BODY PRESSURE SEAL TO FRONT SPAR OUTBD (continued)											
2011B	20	HQ	AZ		63-7	27-81-22	D39904	23			SP03470		9		YC051-YD158
2011B	20	HQ	AZ		63-6	27-81-22	D39904	23			SP03470		9		YD160-YR328
2011R	20	HQ	AZ		0-0	27-81-22	D39904	22			SP03468		9		ALL
2011Z			AZ		0-0	27-81-22	D39904	S/R			GD04110	ST..	E		ALL
2012B	20	HQ	BA		58-1	27-81-22	D39904	25			SP03474		9		YC051-YD158
2012B	20	HQ	BA		58-0	27-81-22	D39904	25			SP03474		9		YD160-YR328
2012R	20	HQ	BA		0-0	27-81-22	D39904	24			SP03472		9		ALL
2012Z			BA		0-0	27-81-22	D39904	S/R			GD04112	ST..	E		ALL
2601B	20	HQ	SA		24-2	27-81-22	D39904	12			D10595		2		YC051-YD158
2601B	20	HQ	SA		24-3	27-81-22	D39904	12			D10595		2		YD160-YR328
2601R	20	HQ	SA		0-0	27-81-22	D39904	11			D10595		1		ALL
2601Z			SA		0-0	27-81-22	D39904	S/R			D10595	S/R			ALL
2602B	20	HQ	SB		34-3	27-81-22	D39904	16			D10597		2		ALL
2602R	20	HQ	SB		0-0	27-81-22	D39904	15			D10597		1		ALL
2602Z			SB		0-0	27-81-22	D39904	S/R			D10597	S/R			ALL
2603B	20	HQ	SC		45-6	27-81-22	D39904	30			D10599		2		ALL
2603R	20	HQ	SC		0-0	27-81-22	D39904	29			D10599		1		ALL
2603Z			SC		0-0	27-81-22	D39904	S/R			D10599	S/R			ALL
A-B					0-0	27-81-22	S01002	BLU			SP03440		9		ALL
A-R					0-0	27-81-22	S01002	RED			SP03438		9		ALL
A-Y					0-0	27-81-22	S01002	YEL			GD04114	AC..	E		ALL
B-B					0-0	27-81-22	S01003	BLU			SP03446		9		ALL
B-R					0-0	27-81-22	S01003	RED			SP03442		9		ALL
B-Y					0-0	27-81-22	S01003	YEL			GD04118	AC..	E		ALL
C-B					0-0	27-81-22	S01004	BLU			SP03450		9		ALL
C-R					0-0	27-81-22	S01004	RED			SP03448		9		ALL
C-Y					0-0	27-81-22	S01004	YEL			GD04120	AC..	E		ALL
D-B					0-0	27-81-22	S01005	BLU			SP03456		9		ALL
D-R					0-0	27-81-22	S01005	RED			SP03454		9		ALL
D-Y					0-0	27-81-22	S01005	YEL			GD04122	AC..	E		ALL
E-B					0-0	27-81-22	S01006	BLU			SP03460		9		ALL
E-R					0-0	27-81-22	S01006	RED			SP03458		9		ALL
E-Y					0-0	27-81-22	S01006	YEL			GD04124	AC..	E		ALL
F-B					0-0	27-81-22	S01007	BLU			SP03466		9		ALL
F-R					0-0	27-81-22	S01007	RED			SP03462		9		ALL
F-Y					0-0	27-81-22	S01007	YEL			GD04126	AC..	E		ALL
G-B					0-0	27-81-22	S01008	BLU			SP03470		9		ALL
G-R					0-0	27-81-22	S01008	RED			SP03468		9		ALL
G-Y					0-0	27-81-22	S01008	YEL			GD04128	AC..	E		ALL

WIRE LIST

D280A108

91-21-11

Section W1280

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity

W1288		286A1288			RIGHT WING BODY PRESSURE SEAL TO FRONT SPAR OUTBD (continued)											
H-B						0-0	27-81-22	S01009		BLU		SP03474		9		ALL
H-R						0-0	27-81-22	S01009		RED		SP03472		9		ALL
H-Y						0-0	27-81-22	S01009		YEL		GD04130	AC..	E		ALL

For training purposes only!

WIRE LIST
D280A108

91-21-11
Section W1280
Page 8 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY	Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice
W1662	286A1662	LEFT WING/BODY PRESSURE SEAL TO FRONT SPAR			
1001	18	HP AA	6-1 33-42-11	D39907 14	T00043 HV GW YC051-YD158, YL951-YR328
1001Z		AA	0-0 33-42-11	D39907 S/R	GD03906 ST.. GW *1 YC051-YD158, YL951-YR328
1002	12	HE AB	1-10 33-42-11	T00043 G GW	GD00198 AC.. N *1 YC051-YD158
1002	12	HE AB	2-2 33-42-11	T00043 G GW	GD00198 AC.. N *1 YL951-YR328
1002Z		AB	0-0 33-42-11	GD03906 ST.. GW *1	GD00198 AC.. N *1 YC051-YD158, YL951-YR328
1003	12	HE AC	3-9 33-42-11	T00043 LV GW	L00320 =P GW YC051-YD158, YL951-YR328
1003Z		AC	0-0 33-42-11	GD03906 ST.. GW *1	L00320 FA YC051-YD158, YL951-YR328
1004	12	HE AD	2-9 33-42-11	L00320 =G GW	GD00194 AC.. N *1 YC051-YD158
1004	12	HE AD	2-5 33-42-11	L00320 =G GW	GD00194 AC.. N *1 YL951-YR328
1004Z		AD	0-0 33-42-11	GD00194 AC.. N *1	L00320 FA YC051-YD158, YL951-YR328
1005	16	HP AE	6-5 33-45-11	D39907 12	L00330 =P G3 YC051-YD153
1005	16	HP AE	6-5 33-45-11	D39907 7	L00330 =P G3 YD154-YD158, YL951-YR328
1005Z		AE	0-0 33-45-11	D39907 S/R	L00330 FB YC051-YD158, YL951-YR328
1006	16	HP AF	1-11 33-45-11	L00330 =G G3	GD00194 AC.. GW *2 YC051-YD158
1006	16	HP AF	1-8 33-45-11	L00330 =G G3	GD00194 AC.. GW *2 YL951-YR328
1006Z		AF	0-0 33-45-11	L00330 FB	GD00194 AC.. GW *2 YC051-YD158, YL951-YR328
1007	20	HP AG	19-0 30-11-11	D39907 5	D00732 2 YC051-YD158
1007	20	HP AG	19-1 30-11-11	D39907 5	D00732 2 YL951-YR328
1007Z		AG	0-0 30-11-11	D39907 S/R	D00732 S/R YC051-YD158, YL951-YR328
1008	20	HP AH	19-0 30-11-11	D39907 3	D00732 1 YC051-YD158
1008	20	HP AH	19-1 30-11-11	D39907 3	D00732 1 YL951-YR328
1008Z		AH	0-0 30-11-11	D39907 S/R	D00732 S/R YC051-YD158, YL951-YR328
1009	20	HE AJ	1-7 30-11-11	D00732 3	GD01100 AC.. E * YC051-YD158
1009	20	HE AJ	1-10 30-11-11	D00732 3	GD01100 AC.. E * YL951-YR328
1009Z		AJ	0-0 30-11-11	D00732 S/R	GD01100 AC.. E * YC051-YD158, YL951-YR328
1010	20	HP AK	64-3 33-43-11	D39907 18	D11046 6 YC051-YD158
1010	20	HP AK	64-1 33-43-11	D39907 18	D11046 6 YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W1660

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W1662	286A1662				LEFT WING/BODY PRESSURE SEAL TO FRONT SPAR (continued)											
1010Z				AK	0-0	33-43-11		D39907		S/R		D11046		S/R		YC051-YD158, YL951-YR328
1011	20	HP	AM		64-10	33-44-12		D39907		11		D11042		1		YC051-YD158
1011	20	HP	AM		64-8	33-44-12		D39907		11		D11042		1		YL951-YR328
1011Z				AM	0-0	33-44-12		D39907		S/R		D11042		S/R		YC051-YD158, YL951-YR328
1012	20	HP	AN		3-7	28-43-11		D39907		9		D00870		3		YC051-YD158
1012	20	HP	AN		3-5	28-43-11		D39907		9		D00870		3		YL951-YR328
1012Z				AN	0-0	28-43-11		D39907		S/R		GD00166		DC..	GW	YC051-YD158, YL951-YR328
1013	20	HL			1-9	28-43-11		D00870		2		GD00166		DC..	GW	YC051-YD158
1013	20	HL			1-7	28-43-11		D00870		2		GD00166		DC..	GW	YL951-YR328
2001B	20	HQ	AQ		47-9	28-44-11		D39907		21		SP03478		9		YC051-YD158
2001B	20	HQ	AQ		48-0	28-44-11		D39907		21		SP03478		9		YL951-YR328
2001R	20	HQ	AQ		0-0	28-44-11		D39907		20		SP03476		9		YC051-YD158, YL951-YR328
2001Z				AQ	0-0	28-44-11		D39907		S/R		GD04132		ST..	E	YC051-YD158, YL951-YR328
M-B					0-0	28-44-11		S00574		=B		SP03478		9		YC051-YC068
M-B				AI	0-0	28-44-11		S00574		=B		SP03478		9		YC070-YD158, YL951-YR328
M-R					0-0	28-44-11		S00574		=A		SP03476		9		YC051-YC068
M-R				AI	0-0	28-44-11		S00574		=A		SP03476		9		YC070-YD158, YL951-YR328
W1664	286A1664				RIGHT WING-WING/BODY TO FRONT SPAR AND P15 REFUELING PANEL											
0023	16	HL			1-10	28-44-11		D00894		1		GD04148		ST..	E	YC051-YC057, YL951-YR328
0023	16	HL			1-11	28-44-11		D00894		1		GD04148		ST..	E	YC058-YD158
0025	16	HL			2-1	28-44-11		D00892		1		GD04148		ST..	E	YC051-YD158, YL951-YR328
0027	16	HL			2-3	28-44-11		D00890		1		GD04148		ST..	E	YC051-YC057
0027	16	HL			2-1	28-44-11		D00890		1		GD04148		ST..	E	YC058
0027	16	HL			2-2	28-44-11		D00890		1		GD04148		ST..	E	YC059-YD158, YL951-YR328
0034	20	HL			3-2	28-44-11		D00894		2		GD00240		DC..	E	YC051-YD158, YL951-YR328
0035	20	HL			1-3	28-44-11		D00894		3		SM00001		9		YC051-YD158
0035	20	HL			1-2	28-44-11		D00894		3		SM00001		9		YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W1660

Page 2

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W1664	286A1664				RIGHT WING-WING/BODY TO FRONT SPAR AND P15 REFUELING PANEL (continued)											
0036	20		HL		3-2	28-44-11	D00892		2		GD00240	DC..	E		YC051-YD158, YL951-YR328	
0037	20		HL		1-2	28-44-11	D00892		3		SM00003		9		YC051-YC057	
0037	20		HL		1-1	28-44-11	D00892		3		SM00003		9		YC058-YD158, YL951-YR328	
0038	20		HL		3-2	28-44-11	D00890		2		GD00240	DC..	E		YC051-YD158, YL951-YR328	
0039	20		HL		1-4	28-44-11	D00890		3		SM00009		9		YC051-YC057	
0039	20		HL		1-1	28-44-11	D00890		3		SM00009		9		YC058-YD158, YL951-YR328	
1001	18		HP	AA	6-5	33-42-11	D39908		16		T00044	HV	GW		YC051-YD158	
1001	18		HP	AA	6-3	33-42-11	D39908		16		T00044	HV	GW		YL951-YR328	
1001Z				AA	0-0	33-42-11	D39908		S/R		GD04032	ST..	GW	*1	YC051-YD158, YL951-YR328	
1002	12		HE	AB	2-3	33-42-11	T00044		G	GW	GD00208	AC..	N	*1	YC051-YD158	
1002	12		HE	AB	2-4	33-42-11	T00044		G	GW	GD00208	AC..	N	*1	YL951-YR328	
1002Z				AB	0-0	33-42-11	GD04032		ST..	GW	*1	GD00208	AC..	N	*1	YC051-YD158, YL951-YR328
1003	12		HE	AC	4-0	33-42-11	T00044		LV	GW	L00321	=P	GW		YC051-YD158	
1003	12		HE	AC	3-10	33-42-11	T00044		LV	GW	L00321	=P	GW		YL951-YR328	
1003Z				AC	0-0	33-42-11	GD04032		ST..	GW	*1	L00321			FA	YC051-YD158, YL951-YR328
1004	12		HE	AD	2-11	33-42-11	L00321		=G	GW	GD00204	AC..	N	*1	YC051-YD158, YL951-YR328	
1004Z				AD	0-0	33-42-11	L00321				FA	GD00204	AC..	N	*1	YC051-YD158, YL951-YR328
1005	16		HP	AE	6-7	33-45-11	D39908		17		L00331	=P	G3		YC051-YD153	
1005	16		HP	AE	6-7	33-45-11	D39908		10		L00331	=P	G3		YD154-YD158	
1005	16		HP	AE	6-6	33-45-11	D39908		10		L00331	=P	G3		YL951-YR328	
1005Z				AE	0-0	33-45-11	D39908		S/R		L00331				FB	YC051-YD158, YL951-YR328
1006	16		HP	AF	2-3	33-45-11	L00331		=G	G3	GD00204	AC..	GW	*2	YC051-YD158, YL951-YR328	
1006Z				AF	0-0	33-45-11	L00331				FB	GD00204	AC..	GW	*2	YC051-YD158, YL951-YR328
1007	20		HP	AG	19-1	30-11-11	D39908		5		D00734		2		YC051-YD158	
1007	20		HP	AG	19-3	30-11-11	D39908		5		D00734		2		YL951-YR328	
1007Z				AG	0-0	30-11-11	D39908		S/R		D00734		S/R		YC051-YD158, YL951-YR328	

WIRE LIST

D280A108

91-21-11

Section W1660

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1664	286A1664			RIGHT WING-WING/BODY TO FRONT SPAR AND P15 REFUELING PANEL (continued)											
1008	20	HP	AH		19-1	30-11-11	D39908		8		D00734		1		YC051-YD158
1008	20	HP	AH		19-3	30-11-11	D39908		8		D00734		1		YL951-YR328
1008Z			AH		0-0	30-11-11	D39908		S/R		D00734		S/R		YC051-YD158, YL951-YR328
1009	20	HP	AJ		1-7	30-11-11	D00734		3		GD01034	AC..	E	*	YC051-YD158
1009	20	HP	AJ		2-0	30-11-11	D00734		3		GD01034	AC..	E	*	YL951-YR328
1009Z			AJ		0-0	30-11-11	D00734		S/R		GD01034	AC..	E	*	YC051-YD158, YL951-YR328
1010	20	HP	AK		64-2	33-43-11	D39908		20		D11044		6		YC051-YD158, YL951-YR328
1010Z			AK		0-0	33-43-11	D39908		S/R		D11044		S/R		YC051-YD158, YL951-YR328
1011	20	HP	AM		65-0	33-44-12	D39908		19		D11040		1		YC051-YD158, YL951-YR328
1011Z			AM		0-0	33-44-12	D39908		S/R		D11040		S/R		YC051-YD158, YL951-YR328
1012	20	HP	AN		4-1	28-44-11	D04578J		12		SP00928		9		YC051-YD158
1012	20	HP	AN		3-11	28-44-11	D04578J		12		SP00928		9		YL951-YR328
1012Z			AN		0-0	28-44-11	D04578J		S/R		GD01054	ST..	E		YC051-YD158, YL951-YR328
1013	18	HP	BA		28-0	28-44-11	D39908		12		SP00928		9		YC051-YD158
1013	18	HP	BA		28-1	28-44-11	D39908		12		SP00928		9		YL951-YR328
1013Z			BA		0-0	28-44-11	D39908		S/R		GD00240	ST..	E		YC051-YD158, YL951-YR328
1014	20	HP	AP		28-6	28-44-11	D39908		28		D04578J		16		YC051-YD158, YL951-YR328
1014Z			AP		0-0	28-44-11	D39908		S/R		D04578J		S/R		YC051-YD158, YL951-YR328
1015	20	HP	AQ		28-6	28-44-11	D39908		29		D04578J		1		YC051-YD158, YL951-YR328
1015Z			AQ		0-0	28-44-11	D39908		S/R		D04578J		S/R		YC051-YD158, YL951-YR328
1016	20	HP	AR		3-2	28-44-11	D04578J		10		GD01054	DC..	E	*	YC051-YD158, YL951-YR328
1016Z			AR		0-0	28-44-11	D04578J		S/R		GD01054	DC..	E	*	YC051-YD158, YL951-YR328
1017	20	HP	AS		2-0	28-44-11	D04578J		9		SM00001		9		YC051-YD158
1017	20	HP	AS		1-11	28-44-11	D04578J		9		SM00001		9		YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W1660

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice
W1664	286A1664				RIGHT WING-WING/BODY TO FRONT SPAR AND P15 REFUELING PANEL (continued)										
1017Z				AS	0-0	28-44-11	D04578J	S/R			GD00462	ST..	E	*1	YC051-YD158, YL951-YR328
1018	20	HP	AT		21-8	28-44-11	D04578J	7			SP01734		9		YC051-YD158
1018	20	HP	AT		22-3	28-44-11	D04578J	7			SP01734		9		YL951-YR328
1018Z				AT	0-0	28-44-11	D04578J	S/R			GD04142	ST..	E		YC051-YD158, YL951-YR328
1019	20	HP	AU		26-10	28-44-11	SP00888		9		D04578J	14			YC051-YD158
1019	20	HP	AU		27-1	28-44-11	SP00888		9		D04578J	14			YL951-YR328
1019Z				AU	0-0	28-44-11	GD00262	ST..	GW		D04578J	S/R			YC051-YD158, YL951-YR328
1020	20	HP	AV		2-4	28-44-11	D04578J	18			SM00003		9		YC051-YD158
1020	20	HP	AV		2-3	28-44-11	D04578J	18			SM00003		9		YL951-YR328
1020Z				AV	0-0	28-44-11	D04578J	S/R			GD00870	ST..	E	*1	YC051-YD158, YL951-YR328
1021	20	HP	AW		2-4	28-44-11	D04578J	8			SM00009		9		YC051-YC057
1021	20	HP	AW		2-5	28-44-11	D04578J	8			SM00009		9		YC058-YD158
1021	20	HP	AW		2-3	28-44-11	D04578J	8			SM00009		9		YL951-YR328
1021Z				AW	0-0	28-44-11	D04578J	S/R			GD00870	ST..	E	*2	YC051-YD158, YL951-YR328
1022	20	HP	AX		27-3	28-44-11	D39908	31			SM00009		9		YC051-YC057
1022	20	HP	AX		27-4	28-44-11	D39908	31			SM00009		9		YC058-YD158, YL951-YR328
1022Z				AX	0-0	28-44-11	D39908	S/R			GD00870	ST..	E	*2	YC051-YD158, YL951-YR328
1023	20	HP	AI		27-4	28-44-11	D39908	32			SM00003		9		YL951-YR328
1023Z				AI	0-0	28-44-11	D39908	S/R			GD00870	ST..	E	*1	YL951-YR328
1024	20	HP	AY		21-9	28-44-11	SP01732		9		SM00001		9		YC051-YD158, YL951-YR328
1024Z				AY	0-0	28-44-11	GD04142	ST..	E		GD00462	ST..	E	*1	YC051-YD158, YL951-YR328
1026	20	HP	AZ		25-7	28-44-11	SP00998		9		SM00003		9		YC051-YC057
1026	20	HP	AZ		25-8	28-44-11	SP00998		9		SM00003		9		YC058-YD158
1026	20	HP	AZ		25-11	28-44-11	SP00998		9		SM00003		9		YL951-YR328
1026Z				AZ	0-0	28-44-11	GD00262	ST..	GW		GD00870	ST..	E	*1	YC051-YD158, YL951-YR328
1032	20	HP	BH		3-7	28-43-11	D39908	30			D00874	3			YC051-YD158, YL951-YR328
1032Z				BH	0-0	28-43-11	D39908	S/R			GD00162	DC..	GW		YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W1660

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1664	286A1664					RIGHT WING-WING/BODY TO FRONT SPAR AND P15 REFUELING PANEL (continued)									
1033	20		HL		1-10	28-43-11	D00874		2		GD00162	DC..	GW		YC051-YD158
1033	20		HL		2-3	28-43-11	D00874		2		GD00162	DC..	GW		YL951-YR328
1034	20		HP	BK	28-6	28-44-11	D39908		33		D04578J		21		YC051-YD158, YL951-YR328
1034Z				BK	0-0	28-44-11	D39908		S/R		D04578J		S/R		YC051-YD158, YL951-YR328
1035	20		HL		4-1	28-44-11	D04578J		11		SP00280		9		YC051-YD158
1035	20		HL		3-11	28-44-11	D04578J		11		SP00280		9		YL951-YR328
2001B	20		HQ	BC	28-6	28-41-11	D39908		23		D04578J		5		YC051-YD158, YL951-YR328
2001R	20		HQ	BC	0-0	28-41-11	D39908		22		D04578J		4		YC051-YD158, YL951-YR328
2001Z				BC	0-0	28-41-11	D39908		S/R		D04578J		S/R		YC051-YD158, YL951-YR328
3002B	20		M3	BB	28-11	23-41-11	D39908		26		SP00425		9		YC051-YD158
3002B	20		M3	BB	29-0	23-41-11	D39908		26		SP00425		9		YL951-YR328
3002R	20		M3	BB	0-0	23-41-11	D39908		25		SP00421		9		YC051-YD158, YL951-YR328
3002Y	20		M3	BB	0-0	23-41-11	D39908		27		SP00423		9		YC051-YD158, YL951-YR328
3002ZI				BB	0-0	23-41-11	D39908		11		SP00421		DED		YC051-YD158, YL951-YR328
3002ZO				BB	0-0	23-41-11	D39908		S/R		GD04148		ST..	E	YC051-YD158, YL951-YR328
A-B					0-0	28-44-11	L00280		= A		SP00928		9		YC051-YD158, YL951-YR328
A-C					0-0	28-44-11	L00279		= A		SP00928		9		YC051-YD158, YL951-YR328
A-D					0-0	28-44-11	SP00280			9	S00156		B		YC051-YD158, YL951-YR328
A-E					0-0	28-44-11	S00156		A		GD01054		DC..	E	YC051-YD158, YL951-YR328
A-J					0-0	28-44-11	S00578		= A		SP01732		9		YC051-YC068
A-J				AL	0-0	28-44-11	S00578		= A		SP01732		9		YC070-YD158, YL951-YR328
A-K					0-0	28-44-11	S00578		= B		SP01734		9		YC051-YC068
A-K				AL	0-0	28-44-11	S00578		= B		SP01734		9		YC070-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W1660

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W1664	286A1664				RIGHT WING-WING/BODY TO FRONT SPAR AND P15 REFUELING PANEL (continued)										
A-U					0-0	23-41-11	D06013		BLU		SP00425		9		YC051-YD158, YL951-YR328
A-V					0-0	23-41-11	D06013		RED		SP00421		9		YC051-YD158, YL951-YR328
A-W					0-0	23-41-11	D06013		BLK		SP00423		9		YC051-YD158, YL951-YR328
B-A					0-0	28-44-11	S00576		= A		SP00998		9		YC051-YC068
B-A				AO	0-0	28-44-11	S00576		= A		SP00998		9		YC070-YD158, YL951-YR328
B-B					0-0	28-44-11	S00576		= B		SP00888		9		YC051-YC068
B-B				AO	0-0	28-44-11	S00576		= B		SP00888		9		YC070-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W1660

Page 7 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2004	286A2004			WINDOW NO.2 WINDSHIELD HEAT BUNDLE (NN2)											
1001	20	X1	AA		2-8	30-41-11	D10572		4		A00013	= A	E		YC051-YD158
1001	20	X1	AA		2-8	30-41-12	D10572		4		A00013	= A	E		YL951-YL968, YN231-YN236, YN501-YR328
1001Z			AA		0-0	30-41-11	D10572		DED		A00013	DED			YC051-YD158
1001Z			AA		0-0	30-41-12	D10572		DED		A00013	DED			YL951-YL968, YN231-YN236, YN501-YR328
5501	20	PA			2-7	30-41-11	D10572		3		A00013	= B	E		YC051-YD158
5501	20	PA			2-7	30-41-12	D10572		3		A00013	= B	E		YL951-YL968, YN231-YN236, YN501-YR328
5502	20	PA			1-2	30-41-11	D10572		2		A00013	= D	C		YC051-YD158
5502	20	PA			1-2	30-41-12	D10572		2		A00013	= D	C		YL951-YL968, YN231-YN236, YN501-YR328
5503	20	PA			1-2	30-41-11	D10572		1		A00013	= C	C		YC051-YD158
5503	20	PA			1-2	30-41-12	D10572		1		A00013	= C	C		YL951-YL968, YN231-YN236, YN501-YR328
W2006	286A2006			WINDOW NO.2 COILED CORD WINDSHIELD BUNDLE (NN2)											
1001R	24	BF	1A		2-7	30-41-11	D10570		1		D10562		1		YC051-YD158
1001Z			1A		0-0	30-41-11	D10570		DED		D10562			AA	YC051-YD158
1002G	24	BF	1B		0-0	30-41-11	D10570		2		D10562		2		YC051-YD158
1002Z			1B		0-0	30-41-11	D10570		DED		D10562			AA	YC051-YD158
2001K	20	BF	1C		0-0	30-41-11	D10570		3		D10562		3		YC051-YD158
2001W	20	BF	1C		0-0	30-41-11	D10570		4		D10562		4		YC051-YD158
FRAA					0-0	30-41-11	D10562		5		D10562			AA	YC051-YD158

WIRE LIST

D280A108

91-21-11

Section W2000

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I	W2012	286A2012			WINDOW NO.2 WINDSHIELD HEAT BUNDLE (NN2)											
I	1001	20	X1	AA		2-8	30-41-11	D10560		4		A00009	=A	E		YR312-YR328
I	1001Z			AA		0-0	30-41-11	D10560		DED		A00009	DED			YR312-YR328
I	5501	20	PA			2-7	30-41-11	D10560		3		A00009	=B	E		YR312-YR328
I	5502	20	PA			1-2	30-41-11	D10560		2		A00009	=D	C		YR312-YR328
I	5503	20	PA			1-2	30-41-11	D10560		1		A00009	=C	C		YR312-YR328

WIRE LIST

D280A108

91-21-11

Section W2010

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

	Bundle No.	Part Number			Description		From				To				Effectivity
	Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	
I	W2022	286A2022			P9 TO E1-3										
I	0501	24		PK		19-0	32-42-11	D41400P				D40914P	1		ALL
I	0502	24		PK		19-0	32-42-11	D41400P				D40914P	2		ALL
I	0503	24		PK		19-0	32-42-11	D41400P				D40914P	3		ALL
I	0504	24		PK		19-0	32-42-11	D41400P				D40914P	4		ALL
I	0505	24		PK		19-0	32-42-11	D41400P				D40914P	5		ALL
I	0506	24		PK		19-0	32-42-11	D41400P				D40914P	6		ALL
I	0507	24		PK		19-0	32-42-11	D41400P				D40914P	7		ALL
I	0508	24		PK		19-0	32-42-11	D41400P				D40914P	8		ALL
I	0509	24		PK		19-0	32-42-11	D41400P				D40914P	9		ALL
I	0510	24		PK		19-0	32-42-11	D41400P				D40914P	10		ALL
I	0511	24		PK		19-0	32-42-11	D41400P				D40914P	11		ALL
I	0512	24		PK		19-0	32-41-11	D41400P				D40914P	12		ALL
I	0513	24		PK		19-0	32-41-11	D41400P				D40914P	13		ALL

WIRE LIST

D280A108

91-21-11

Section W2020

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2030		286A2030			AP0900A DISC BRKT TO AP0600B DISC BRKT (SN2)											
1001		18		X1	AA	10-1	33-11-31	D40924P	15	18		SP00300		S		ALL
1001Z					AA	0-0	33-11-31	D40924P		S/R		SP00300			AD	ALL
5501		24		PK		9-9	31-22-11	D46052P	1			D40924P	27			ALL
5502		24		PK		9-9	31-22-11	D46052P	2			D40924P	28			ALL
5503		16		CQ		9-9	33-11-11	D46052P	23			D40924P	4			ALL
5504		16		CQ		16-3	33-11-11	TB0806V	A005	1		D40924P	8			ALL
5505		16		CQ		10-1	33-11-11	SP02138		S		D40924P	10			ALL
5506		16		PA		9-9	33-11-32	D46052P	21			D40924P	2			ALL
5508		16		CQ		8-9	33-11-32	SP02205		S		D40924P	6			ALL
5509		20		PA		9-9	33-18-11	D46052P	3			D40924P	17			ALL
5511		20		CQ		9-9	33-18-21	D46052P	5			D40924P	12			ALL
5512		20		CQ		9-9	33-18-21	D46052P	6			D40924P	9			ALL
5513		20		CQ		9-9	33-18-21	D46052P	7			D40924P	13			ALL
5514		20		CQ		9-9	33-18-23	D46052P	8			D40924P	11			ALL
5516		20		PA		9-9	SPARE	D46052P	9			D40924P	5			ALL
5517		20		PA		9-9	33-18-62	D46052P	13			D40924P	20			ALL
5520		20		CQ		9-9	33-18-22	D46052P	15			D40924P	22			ALL
5521		20		PA		9-9	33-18-62	D46052P	10			D40924P	19			ALL
5522		20		PA		9-9	SPARE	D46052P	11			D40924P	3			ALL
5523		20		PA		9-9	SPARE	D46052P	12			D40924P	7			ALL
5524		20		CQ		9-9	31-52-11	D46052P	16			D40924P	24			ALL
5525		20		PA		9-9	33-18-11	D46052P	4			D40924P	18			ALL
5526		20		PA		9-9	SPARE	D46052P	26			D40924P	25			ALL
5527		20		PA		9-9	SPARE	D46052P	27			D40924P	26			ALL
5528		22		PA		9-9	29-32-11	D46052P	25			D40924P	23			ALL
5529		22		PA		9-9	32-31-11	D46052P	29			D40924P	31			ALL
W2035		286A2035			P5, E5-2											
0002		22		PA		32-9	34-61-12	D01817	8			D45235J	A03			YC051-YC052
0002		22		PA		32-10	34-61-12	D01817	8			D45235J	A03			YC053-YC058
0002		22		PA		32-11	34-61-12	D01817	8			D45235J	A03			YC059-YC064
0002		22		PA		33-2	34-61-12	D01817	8			D45235J	A03			YC065-YR328
0003		22		PA		32-9	34-61-12	D01817	9			D45235J	A04			YC051-YC052
0003		22		PA		32-10	34-61-12	D01817	9			D45235J	A04			YC053-YC058
0003		22		PA		32-11	34-61-12	D01817	9			D45235J	A04			YC059-YC064
0003		22		PA		33-2	34-61-12	D01817	9			D45235J	A04			YC065-YR328
0004		22		PA		32-9	34-61-12	D01817	10			D45235J	A02			YC051-YC052
0004		22		PA		32-10	34-61-12	D01817	10			D45235J	A02			YC053-YC058
0004		22		PA		32-11	34-61-12	D01817	10			D45235J	A02			YC059-YC064

WIRE LIST

D280A108

91-21-11

Section W2030

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2035	286A2035			P5, E5-2 (continued)											
0004	22		PA		33-2	34-61-12	D01817		10		D45235J	A02			YC065-YR328
0005	22		PA		32-9	34-61-12	D01817		11		D45235J	A05			YC051-YC052
0005	22		PA		32-10	34-61-12	D01817		11		D45235J	A05			YC053-YC058
0005	22		PA		32-11	34-61-12	D01817		11		D45235J	A05			YC059-YC064
0005	22		PA		33-2	34-61-12	D01817		11		D45235J	A05			YC065-YR328
0006	24		PK		30-7	34-61-17	D45235J		A06		TB0504X	B013	1A		YC051-YC052
0006	24		PK		30-4	34-61-17	D45235J		A06		TB0504X	B013	1A		YC053-YC058
0006	24		PK		30-3	34-61-17	D45235J		A06		TB0504X	B013	1A		YC059-YC064
0006	24		PK		30-8	34-61-17	D45235J		A06		TB0504X	B013	1A		YC065-YR328
0007	24		PK		30-7	34-61-17	D45235J		A07		TB0504X	B014	1A		YC051-YC052
0007	24		PK		30-4	34-61-17	D45235J		A07		TB0504X	B014	1A		YC053-YC058
0007	24		PK		30-3	34-61-17	D45235J		A07		TB0504X	B014	1A		YC059-YC064
0007	24		PK		30-8	34-61-17	D45235J		A07		TB0504X	B014	1A		YC065-YR328
0008	24		PK		30-7	34-61-17	D45235J		A08		TB0504X	B015	1A		YC051-YC052
0008	24		PK		30-4	34-61-17	D45235J		A08		TB0504X	B015	1A		YC053-YC058
0008	24		PK		30-3	34-61-17	D45235J		A08		TB0504X	B015	1A		YC059-YC064
0008	24		PK		30-8	34-61-17	D45235J		A08		TB0504X	B015	1A		YC065-YR328
0009	24		PK		30-7	34-61-17	D45235J		A09		TB0504X	A013	1A		YC051-YC052
0009	24		PK		30-4	34-61-17	D45235J		A09		TB0504X	A013	1A		YC053-YC058
0009	24		PK		30-3	34-61-17	D45235J		A09		TB0504X	A013	1A		YC059-YC064
0009	24		PK		30-8	34-61-17	D45235J		A09		TB0504X	A013	1A		YC065-YR328
0010	24		PK		30-7	34-61-17	D45235J		A10		TB0504X	A014	1A		YC051-YC052
0010	24		PK		30-4	34-61-17	D45235J		A10		TB0504X	A014	1A		YC053-YC058
0010	24		PK		30-3	34-61-17	D45235J		A10		TB0504X	A014	1A		YC059-YC064
0010	24		PK		30-8	34-61-17	D45235J		A10		TB0504X	A014	1A		YC065-YR328
0011	22		PA		31-8	34-21-11	D45235J		A11		D02169	9			YC051-YC052, YC059-YC064
0011	22		PA		31-10	34-21-11	D45235J		A11		D02169	9			YC053-YC058, YC065-YR328
0012	24		PK		31-8	34-21-11	D45235J		A12		D02169	24			YC051-YC052, YC059-YC064
0012	24		PK		31-10	34-21-11	D45235J		A12		D02169	24			YC053-YC058, YC065-YR328
0013	24		PK		31-8	34-21-11	D45235J		A13		D02169	25			YC051-YC052, YC059-YC064
0013	24		PK		31-10	34-21-11	D45235J		A13		D02169	25			YC053-YC058, YC065-YR328
0014	24		PK		3-4	34-21-11	TB0503Y		B007	1A	D02169	3			YC051-YC052
0014	24		PK		3-6	34-21-11	TB0503Y		B007	1A	D02169	3			YC053-YC064

WIRE LIST

D280A108

91-21-11

Section W2030

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2035	286A2035			P5, E5-2 (continued)											
0014	24	PK			3-3	34-21-11	TB0503Y	B007	1A		D02169	3			YC065-YR328
0015	24	PK			31-8	34-21-11	D45235J	A15			D02169	4			YC051-YC052, YC059-YC064
0015	24	PK			31-10	34-21-11	D45235J	A15			D02169	4			YC053-YC058, YC065-YR328
0016	22	PA			31-7	34-21-11	D02171	11			D45235J	A01			YC051-YC052
0016	22	PA			31-9	34-21-11	D02171	11			D45235J	A01			YC053-YC058
0016	22	PA			31-8	34-21-11	D02171	11			D45235J	A01			YC059-YC064
0016	22	PA			31-11	34-21-11	D02171	11			D45235J	A01			YC065-YD157
0016	22	PA			31-11	34-21-11	D45235J	A01			D02171	11			YD158-YR328
0017	22	PA			31-7	34-21-11	D45235J	A17			D02171	12			YC051-YC052
0017	22	PA			31-9	34-21-11	D45235J	A17			D02171	12			YC053-YC058
0017	22	PA			31-8	34-21-11	D45235J	A17			D02171	12			YC059-YC064
0017	22	PA			31-11	34-21-11	D45235J	A17			D02171	12			YC065-YR328
0018	22	PA			31-7	34-21-11	D45235J	A18			D02171	13			YC051-YC052
0018	22	PA			31-9	34-21-11	D45235J	A18			D02171	13			YC053-YC058
0018	22	PA			31-8	34-21-11	D45235J	A18			D02171	13			YC059-YC064
0018	22	PA			31-11	34-21-11	D45235J	A18			D02171	13			YC065-YR328
0019	22	PA			31-7	34-21-11	D45235J	A19			D02171	14			YC051-YC052
0019	22	PA			31-9	34-21-11	D45235J	A19			D02171	14			YC053-YC058
0019	22	PA			31-8	34-21-11	D45235J	A19			D02171	14			YC059-YC064
0019	22	PA			31-11	34-21-11	D45235J	A19			D02171	14			YC065-YR328
0020	22	PA			31-7	34-21-11	D45235J	A20			D02171	17			YC051-YC052
0020	22	PA			31-9	34-21-11	D45235J	A20			D02171	17			YC053-YC058
0020	22	PA			31-8	34-21-11	D45235J	A20			D02171	17			YC059-YC064
0020	22	PA			31-11	34-21-11	D45235J	A20			D02171	17			YC065-YR328
0021	22	PA			31-7	34-21-11	D45235J	B01			D02171	15			YC051-YC052
0021	22	PA			31-9	34-21-11	D45235J	B01			D02171	15			YC053-YC058
0021	22	PA			31-8	34-21-11	D45235J	B01			D02171	15			YC059-YC064
0021	22	PA			31-11	34-21-11	D45235J	B01			D02171	15			YC065-YR328
0022	22	PA			31-7	34-21-11	D45235J	B02			D02171	16			YC051-YC052
0022	22	PA			31-9	34-21-11	D45235J	B02			D02171	16			YC053-YC058
0022	22	PA			31-8	34-21-11	D45235J	B02			D02171	16			YC059-YC064
0022	22	PA			31-11	34-21-11	D45235J	B02			D02171	16			YC065-YR328
0023	22	CQ			32-4	34-21-12	D00644	13			D45235J	B03			YC051-YC052
0023	22	CQ			32-3	34-21-12	D00644	13			D45235J	B03			YC053-YC058
0023	22	CQ			32-5	34-21-12	D00644	13			D45235J	B03			YC059-YC064
0023	22	CQ			32-8	34-21-12	D00644	13			D45235J	B03			YC065-YR328
0024	22	CQ			32-4	34-21-12	D00644	15			D45235J	B04			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W2030

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W2035	286A2035			P5, E5-2 (continued)											
0024	22	CQ		32-3	34-21-12	D00644		15			D45235J	B04			YC053-YC058
0024	22	CQ		32-5	34-21-12	D00644		15			D45235J	B04			YC059-YC064
0024	22	CQ		32-8	34-21-12	D00644		15			D45235J	B04			YC065-YR328
0025	22	CQ		32-4	34-21-12	D00644		14			D45235J	B05			YC051-YC052
0025	22	CQ		32-3	34-21-12	D00644		14			D45235J	B05			YC053-YC058
0025	22	CQ		32-5	34-21-12	D00644		14			D45235J	B05			YC059-YC064
0025	22	CQ		32-8	34-21-12	D00644		14			D45235J	B05			YC065-YR328
0026	24	PK		32-11	31-62-15	D00553		11			D45235J	B06			YC051-YC052
0026	24	PK		33-0	31-62-15	D00553		11			D45235J	B06			YC053-YC058
0026	24	PK		33-1	31-62-15	D00553		11			D45235J	B06			YC059-YC064
0026	24	PK		33-4	31-62-15	D00553		11			D45235J	B06			YC065-YR328
0027	24	PK		32-11	31-62-15	D00553		12			D45235J	B07			YC051-YC052
0027	24	PK		33-0	31-62-15	D00553		12			D45235J	B07			YC053-YC058
0027	24	PK		33-1	31-62-15	D00553		12			D45235J	B07			YC059-YC064
0027	24	PK		33-4	31-62-15	D00553		12			D45235J	B07			YC065-YR328
0028	24	PK		32-11	31-62-15	D00553		13			D45235J	B08			YC051-YC052
0028	24	PK		33-0	31-62-15	D00553		13			D45235J	B08			YC053-YC058
0028	24	PK		33-1	31-62-15	D00553		13			D45235J	B08			YC059-YC064
0028	24	PK		33-4	31-62-15	D00553		13			D45235J	B08			YC065-YR328
0029	22	PA		3-1	31-62-15	D00553		14			GD00507	DC..	1A		YC051-YC052
0029	22	PA		2-9	31-62-15	D00553		14			GD00517	DC..	1A		YC053-YR328
0030	22	PA		31-9	34-16-11	D45235J		B13			D00483		16		YC051-YC052
0030	22	PA		31-8	34-16-11	D45235J		B13			D00483		16		YC053-YC064
0030	22	PA		31-11	34-16-11	D45235J		B13			D00483		16		YC065-YR328
0033	22	PA		30-8	SPARE	D45235J		B11			TB0506X	A013	1A		YC051-YC052
0033	22	PA		30-6	SPARE	D45235J		B11			TB0506X	A013	%A		YC053-YC058
0033	22	PA		30-5	SPARE	D45235J		B11			TB0506X	A013	%A		YC059-YC064
0033	22	PA		30-9	SPARE	D45235J		B11			TB0506X	A013	%A		YC065-YD157
0033	22	PA		30-9	23-42-11	D45235J		B11			TB0506X	A013	1A		YD158-YR328
0034	22	PA		34-1	23-43-11	D45235J		B12			S00032		2 C		YC051-YC052
0034	22	PA		34-2	23-43-11	D45235J		B12			S00032		2 C		YC053-YC064
0034	22	PA		35-2	23-43-11	D45235J		B12			S00032		2 C		YC065-YR328
0035	22	CQ		32-7	22-18-11	D00630		2			D45235J	B16			YC051-YC052
0035	22	CQ		32-9	22-18-11	D00630		2			D45235J	B16			YC053-YC058
0035	22	CQ		32-8	22-18-11	D00630		2			D45235J	B16			YC059-YC064
0035	22	CQ		32-11	22-18-11	D00630		2			D45235J	B16			YC065-YR328
0036	20	PA		2-2	34-21-11	D02169		8			GD00509	ST..	1A		YC051-YC058
0036	20	PA		2-1	34-21-11	D02169		8			GD00509	ST..	1A		YC059-YR328
0037	24	PK		32-11	31-62-15	D00553		34			D45235J	B15			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W2030

Page 4

Nov 12/2012

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2035	286A2035			P5, E5-2 (continued)											
0037	24		PK		33-0	31-62-15	D00553		34		D45235J	B15			YC053-YC058
0037	24		PK		33-1	31-62-15	D00553		34		D45235J	B15			YC059-YC064
0037	24		PK		33-4	31-62-15	D00553		34		D45235J	B15			YC065-YR328
0038	22		PA		3-1	31-62-15	D00553		35		GD00507	DC..	1A		YC051-YC052
0038	22		PA		2-9	31-62-15	D00553		35		GD00517	DC..	1A		YC053-YR328
0039	20		PA		4-10	34-16-11	D00483		15		GD00509	DC..	1A		YC051-YC052
0039	20		PA		4-9	34-16-11	D00483		15		GD00509	DC..	1A		YC053-YC058
0039	20		PA		4-11	34-16-11	D00483		15		GD00509	DC..	1A		YC059-YC064
0039	20		PA		5-0	34-16-11	D00483		15		GD00509	DC..	1A		YC065-YR328
0042	22		CQ		32-7	22-13-11	D00630		1		D45235J	B19			YC051-YC052
0042	22		CQ		32-9	22-13-11	D00630		1		D45235J	B19			YC053-YC058
0042	22		CQ		32-8	22-13-11	D00630		1		D45235J	B19			YC059-YC064
0042	22		CQ		32-11	22-13-11	D00630		1		D45235J	B19			YC065-YR328
0045	22		PA		31-8	34-21-11	D02169		5		D45235J	A16			YC051-YC052, YC059-YC064
0045	22		PA		31-10	34-21-11	D02169		5		D45235J	A16			YC053-YC058, YC065-YR328
0050	22		PA		1-1	34-61-22	D06067J		7		SM00001		W		ALL
0051	22		PA		1-1	34-61-22	D06067J		8		SM00001		W		ALL
0052	22		PA		1-1	34-61-22	D06067J		14		SM00001		W		ALL
0053	24		PK		3-4	34-21-11	TB0503Y	B007	1A		D02169		10		YC051-YC052
0053	24		PK		3-6	34-21-11	TB0503Y	B007	1A		D02169		10		YC053-YC064
0053	24		PK		3-3	34-21-11	TB0503Y	B007	1A		D02169		10		YC065-YR328
0054	24		PK		30-5	34-21-11	TB0503Y	B007	1A		D45235J	A14			YC051-YC052
0054	24		PK		30-6	34-21-11	TB0503Y	B007	1A		D45235J	A14			YC053-YC064
0054	24		PK		30-9	34-21-11	TB0503Y	B007	1A		D45235J	A14			YC065-YR328
0059	22		PA		4-10	34-61-12	D01817		7		TB0503Y	B005	1A		YD158-YR328
2501B	22		X2	AA	31-8	34-21-13	D02169		27		D45235J	B10			YC051-YC052, YC059-YC064
2501B	22		X2	AA	31-10	34-21-13	D02169		27		D45235J	B10			YC053-YC058, YC065-YR328
2501R	22		X2	AA	0-0	34-21-13	D02169		26		D45235J	B09			ALL
2501Z				AA	0-0	34-21-13	D02169	DED			D45235J	PERG	1F		ALL
2502B	24		Y2	AB	24-8	34-61-22	D06067J		12		D45235J	B20			YC051-YC064
2502B	24		Y2	AB	24-11	34-61-22	D06067J		12		D45235J	B20			YC065-YR328
2502R	24		Y2	AB	0-0	34-61-22	D06067J		11		D45235J	B18			ALL
2502Z				AB	0-0	34-61-22	D06067J	DED			D45235J	PERG	1F		ALL
2503B	24		Y2	AC	24-8	34-61-11	D06067J		2		D45235J	B17			YC051-YC064
2503B	24		Y2	AC	24-11	34-61-11	D06067J		2		D45235J	B17			YC065-YR328

WIRE LIST

D280A108

91-21-11

Section W2030

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2035		286A2035			P5, E5-2 (continued)											
2503R		24		Y2	AC	0-0	34-61-11	D06067J		1		D45235J	B14			ALL
2503Z					AC	0-0	34-61-11	D06067J		DED		D45235J	PERG	1F		ALL

For training purposes only!

WIRE LIST

D280A108

91-21-11

Section W2030

Page 6 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To				Effectivity
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W2101	286A2101			LEFT AC ELEX PWR FROM P18 TO E1.											
0001	20	PA		11-11	SPARE	D41801P		1			D41811P	A01			YC051-YC055
0001	20	PA		11-9	SPARE	D41801P		1			D41811P	A01			YC056-YR328
0002	20	PA		11-11	SPARE	D41801P		2			D41811P	A02			YC051-YC055
0002	20	PA		11-9	SPARE	D41801P		2			D41811P	A02			YC056-YR328
0003	20	PA		11-11	SPARE	D41801P		3			D41811P	A03			YC051-YC055
0003	20	PA		11-9	SPARE	D41801P		3			D41811P	A03			YC056-YR328
0004	20	PA		11-11	34-45-11	D41801P		4			D41811P	A04			YC051-YC055
0004	20	PA		11-9	34-45-11	D41801P		4			D41811P	A04			YC056-YR328
0005	20	PA		11-11	22-11-11	D41801P		5			D41811P	A05			YC051-YC055
0005	20	PA		11-9	22-11-11	D41801P		5			D41811P	A05			YC056-YR328
0006	20	PA		11-11	22-18-11	D41801P		6			D41811P	A06			YC051-YC055
0006	20	PA		11-9	22-18-11	D41801P		6			D41811P	A06			YC056-YR328
0007	22	PA		11-11	34-49-11	D41801P		7			D41811P	A07			YC051-YC055
0007	22	PA		11-9	34-49-11	D41801P		7			D41811P	A07			YC056-YR328
0008	22	PA		11-11	SPARE	D41801P		8			D41811P	A08			YC051-YC055
0008	22	PA		11-9	SPARE	D41801P		8			D41811P	A08			YC056-YR328
0009	22	PA		11-11	SPARE	D41801P		9			D41811P	A09			YC051-YC055
0009	22	PA		11-9	SPARE	D41801P		9			D41811P	A09			YC056-YR328
0010	20	PA		11-11	SPARE	D41801P		10			D41811P	A10			YC051-YC055
0010	20	PA		11-9	SPARE	D41801P		10			D41811P	A10			YC056-YR328
0011	20	PA		11-11	SPARE	D41801P		11			D41811P	B01			YC051-YC055
0011	20	PA		11-9	SPARE	D41801P		11			D41811P	B01			YC056-YR328
0012	20	PA		11-11	SPARE	D41801P		12			D41811P	B02			YC051-YC055
0012	20	PA		11-9	SPARE	D41801P		12			D41811P	B02			YC056-YR328
0013	20	PA		11-11	SPARE	D41801P		13			D41811P	B03			YC051-YC055
0013	20	PA		11-9	SPARE	D41801P		13			D41811P	B03			YC056-YR328
0014	20	PA		11-11	SPARE	D41801P		14			D41811P	B04			YC051-YC055
0014	20	PA		11-9	SPARE	D41801P		14			D41811P	B04			YC056-YR328
0015	20	PA		11-11	SPARE	D41801P		15			D41811P	B05			YC051-YC055
0015	20	PA		11-9	SPARE	D41801P		15			D41811P	B05			YC056-YR328
0016	20	PA		13-1	23-11-11	D41801P		16			D40811P	6			YC051-YC052
0016	20	PA		13-6	23-11-11	D41801P		16			D40811P	6			YC053-YC055
0016	20	PA		13-7	23-11-11	D41801P		16			D40811P	6			YC056-YD170
0016	20	PA		118-9	23-11-11	D41801P		16			D40111P	6			YL951-YL999, YR301-YR328
0016	20	PA		99-5	23-11-11	D41801P		16			D40111P	6			YN231-YN501
0017	20	PA		13-1	23-11-11	D41801P		17			D40811P	7			YC051-YC052
0017	20	PA		13-6	23-11-11	D41801P		17			D40811P	7			YC053-YC055
0017	20	PA		13-7	23-11-11	D41801P		17			D40811P	7			YC056-YD170

WIRE LIST

D280A108

91-21-11

Section W2100

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2101	286A2101				LEFT AC ELEX PWR FROM P18 TO E1. (continued)										
0017	20		PA		118-9	23-11-11	D41801P		17		D40111P		7		YL951-YL999, YR301-YR328
0017	20		PA		99-5	23-11-11	D41801P		17		D40111P		7		YN231-YN501
0018	20		PA		13-1	23-11-11	D41801P		18		D40811P		8		YC051-YC052
0018	20		PA		13-6	23-11-11	D41801P		18		D40811P		8		YC053-YC055
0018	20		PA		13-7	23-11-11	D41801P		18		D40811P		8		YC056-YD170
0018	20		PA		118-9	23-11-11	D41801P		18		D40111P		8		YL951-YL999, YR301-YR328
0018	20		PA		99-5	23-11-11	D41801P		18		D40111P		8		YN231-YN501
0019	20		PA		13-1	SPARE	D41801P		19		D40811P		9		YC051-YC052
0019	20		PA		13-6	SPARE	D41801P		19		D40811P		9		YC053-YC055
0019	20		PA		13-7	SPARE	D41801P		19		D40811P		9		YC056-YD170
0020	20		PA		13-1	SPARE	D41801P		20		D40811P		10		YC051-YC052
0020	20		PA		13-6	SPARE	D41801P		20		D40811P		10		YC053-YC055
0020	20		PA		13-7	SPARE	D41801P		20		D40811P		10		YC056-YD170
0021	20		PA		13-1	SPARE	D41801P		21		D40811P		11		YC051-YC052
0021	20		PA		13-6	SPARE	D41801P		21		D40811P		11		YC053-YC055
0021	20		PA		13-7	SPARE	D41801P		21		D40811P		11		YC056-YD170
0022	20		PA		13-1	SPARE	D41801P		22		D40811P		12		YC051-YC052
0022	20		PA		13-6	SPARE	D41801P		22		D40811P		12		YC053-YC055
0022	20		PA		13-7	SPARE	D41801P		22		D40811P		12		YC056-YD170
W2102	286A2102				P18 (L CAB CEILING) DISC TO L CONTROL CABIN AREA (LN2)										
5501	20		PA		26-7	30-41-11	TB0262X	B004	1A		S00190	=B	B	*	YC051-YC052
5501	20		PA		28-3	30-41-11	TB0262X	B004	1A		S00190	=B	B	*	YC053-YD151
5501	20		PA		28-1	30-41-11	TB0262X	B004	1A		S00190	=B	B	*	YD152-YD158
5503	18		CQ		6-9	33-14-12	L00411	=P	C		SP00436		S		ALL
5505	20		PA		19-3	33-17-11	D00796		10		SP00606		S		YC051-YC052
5505	20		PA		18-7	33-17-11	D00796		10		SP00606		S		YC053-YD151
5505	20		PA		17-11	33-17-11	D00796		10		SP00606		S		YD152-YL956, YN231-YN235
5505	20		PA		18-5	33-17-11	D00796		10		SP00606		S		YL957-YL999, YN236-YR328
5507	20		PA		13-7	33-17-11	TB1806X	B007	1A		TB5018		1	E	ALL
5508	20		PA		1-0	33-17-11	SM00002		S		D00796		4		YC051-YC052
5508	20		PA		1-1	33-17-11	SM00002		S		D00796		4		YC053-YD151
5508	20		PA		0-7	33-17-11	SM00002		S		D00796		4		YD152-YR328
5509	20		PA		6-2	33-11-11	D00796		1		SP02138		S		ALL
5510	20		PA		1-10	30-41-11	A00007	=B	E		GD00604	AC..	E		YC051-YD158

WIRE LIST

D280A108

91-21-11

Section W2100

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity								
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2102	286A2102	P18 (L CAB CEILING) DISC TO L CONTROL CABIN AREA (LN2) (continued)											
5511	20	PA	2-4	30-41-11	A00008	=A	E		S00190	=A	B		YC051-YC052
5511	20	PA	2-5	30-41-11	A00008	=A	E		S00190	=A	B		YC053-YD158
5514	20	PA	1-0	33-17-11	SM00002		S		D00796	11			YC051-YC052
5514	20	PA	1-1	33-17-11	SM00002		S		D00796	11			YC053-YD151
5514	20	PA	0-7	33-17-11	SM00002		S		D00796	11			YD152-YR328
5516	20	PA	4-10	30-41-11	A00008	=B	E		A00007	=A	E		YC051-YC052
5516	20	PA	4-9	30-41-11	A00008	=B	E		A00007	=A	E		YC053-YD151
5516	20	PA	6-5	30-41-11	A00008	=B	E		A00007	=A	E		YD152-YD158
5517	18	CQ	4-0	33-14-12	L00410	=G	C		GD01354	AC..	E		ALL
5518	20	PA	3-6	33-11-11	D00796		2		GD00596	AC..	E		ALL
5520	20	PA	18-3	33-17-11	D00796		12		L01003	=P	C		YC051-YC052
5520	20	PA	18-0	33-17-11	D00796		12		L01003	=P	C		YC053-YD151
5521	20	PA	4-5	33-17-11	SM00002		S		TB5018	1	E		YC051-YD151
5521	20	PA	4-11	33-17-11	SM00002		S		TB5018	1	E		YD152-YR328
5522	20	PA	2-2	33-17-11	L01003	=G	C		GD00604	AC..	E		YC051-YD151
5524	20	PA	14-3	30-41-11	S00755	=B	B		S00190	=B	B	*	YC051-YC052
5524	20	PA	14-1	30-41-11	S00755	=B	B		S00190	=B	B	*	YC053-YD151
5524	20	PA	13-11	30-41-11	S00755	=B	B		S00190	=B	B	*	YD152-YD158
5524	20	PA	21-9	30-41-11	TB0262X	B004	1A		S00755	=B	B		YD160-YL956, YN231-YN235
5524	20	PA	21-6	30-41-11	TB0262X	B004	1A		S00755	=B	B		YL957-YL999, YN236-YR328
5525	20	PA	4-2	30-41-11	S00755	=A	B		A00021	=A	E		ALL
5526	20	PA	2-5	30-41-11	A00021	=B	E		GD01290	AC..	E		ALL
5527	18	CQ	18-10	33-14-12	TB0262V	A013	1		SP00436		S		YC051-YC052
5527	18	CQ	20-8	33-14-12	TB0262V	A013	1		SP00436		S		YC053-YL956, YN231-YN235
5527	18	CQ	20-5	33-14-12	TB0262V	A013	1		SP00436		S		YL957-YL999, YN236-YR328
5528	20	PA	6-5	33-17-11	SP00272		S		GD00604	AC..	E		YD152-YR328
5529	20	PA	20-9	33-17-11	D00796		12		L01456	=P	C		YD152-YL956, YN231-YN235
5529	20	PA	21-2	33-17-11	D00796		12		L01456	=P	C		YL957-YL999, YN236-YR328
5530	20	PA	6-8	33-17-11	L01456	=G	C		SP00272		S		YD152-YR328
5533	20	CQ	18-11	33-14-11	D12106	=1			TB0806Y	B009	1A		YC051-YC052
5533	20	CQ	19-5	33-14-11	D12106	=1			TB0806Y	B009	1A		YC053-YR328
5534	20	CQ	2-5	33-14-11	D12108	=1			GD01444	AC..	E		ALL
5535	20	PA	3-6	33-17-11	D00796		6		GD00596	AC..	E		ALL

WIRE LIST

D280A108

91-21-11

Section W2100

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY	Description Fam FT-IN Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W2102	286A2102	P18 (L CAB CEILING) DISC TO L CONTROL CABIN AREA (LN2) (continued)									
B-BG		0-0 33-17-11	L00008	= G			GD00604	AC..	E		YC051-YD151
B-BG		0-0 33-17-11	L03014	= G			SP00272		S		YD152-YR328
B-BP		0-0 33-17-11	L00008	= P			SP00606		S		YC051-YD151
B-BP		0-0 33-17-11	L03014	= P			SP00606		S		YD152-YR328
J-JP		0-0 33-14-12	SP00436		S		L00410	= P			ALL
W2103	286A2103	RIGHT AC ELEX PWR FROM P6 TO E1.									
0001	22	PA	10-0 34-31-21	D46061P	1		D46011J	1			YC051-YD158, YL951-YR328
0002	22	PA	10-0 34-51-21	D46061P	2		D46011J	2			YC051-YD158, YL951-YR328
0003	22	PA	10-0 34-51-21	D46061P	3		D46011J	3			YC051-YD158, YL951-YR328
0004	20	CQ	10-0 22-18-11	D46061P	4		D46011J	4			YC051-YD158, YL951-YR328
0005	20	PA	11-6 SPARE	D46061P	5		D46013P	A05			YC051-YC059, YC065-YD158, YR301-YR328
0005	20	PA	11-6 SPARE	D46061P	CAP	Y	D46013P	A05			YC060-YC064
0005	20	PA	11-7 SPARE	D46061P	5		D46013P	A05			YL951-YN501
0006	20	PA	11-6 SPARE	D46061P	6		D46013P	A06			YC051-YD158, YR301-YR328
0006	20	PA	11-7 SPARE	D46061P	6		D46013P	A06			YL951-YN501
0007	20	CQ	11-6 22-11-11	D46061P	7		D46013P	A07			YC051-YD158, YR301-YR328
0007	20	CQ	11-7 22-11-11	D46061P	7		D46013P	A07			YL951-YN501
0008	20	PA	10-0 34-53-21	D46061P	8		D46011J	8			YC051-YD158, YL951-YR328
0009	22	PA	10-0 34-55-21	D46061P	9		D46011J	9			YC051-YD158, YL951-YR328
0010	22	PA	17-7 23-31-06	D46061P	10		SP03891		S		YC051-YC052, YD158, YL951-YN260
0010	22	PA	13-3 23-31-06	D46061P	10		D48323P	10			YC053-YD157
0011R	22	PH	10-0 26-12-11	D46061P	11		D46011J	11			YC051-YD158, YL951-YR328
0012	20	PA	10-0 SPARE	D46061P	12		D46011J	12			YC051-YD158, YL951-YR328
0013	20	PA	10-0 SPARE	D46061P	13		D46011J	13			YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W2100

Page 4

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2103	286A2103				RIGHT AC ELEX PWR FROM P6 TO E1. (continued)										
0014	24		PK		11-6	27-52-11	D46061P	14			D46013P	A04			YC051-YD158, YR301-YR328
0014	24		PK		11-7	27-52-11	D46061P	14			D46013P	A04			YL951-YN501
0015	24		PK		11-6	27-52-11	D46061P	15			D46013P	A03			YC051-YD158, YR301-YR328
0015	24		PK		11-7	27-52-11	D46061P	15			D46013P	A03			YL951-YN501
0016	20		PA		10-0	SPARE	D46061P	16			D46011J	6			YC051-YD158, YL951-YR328
0017	20		PA		10-0	SPARE	D46061P	17			D46011J	7			YC051-YD158, YL951-YR328
0018	20		PA		11-6	SPARE	D46061P	18			D46013P	A08			YC051-YD158, YR301-YR328
0018	20		PA		11-7	SPARE	D46061P	18			D46013P	A08			YL951-YN501
0019	20		PA		11-6	SPARE	D46061P	19			D46013P	A09			YC051-YD158, YR301-YR328
0019	20		PA		11-7	SPARE	D46061P	19			D46013P	A09			YL951-YN501
0023	16		CQ		11-6	34-21-21	D46061P	23			D46013P	G			YC051-YD158, YR301-YR328
0023	16		CQ		11-7	34-21-21	D46061P	23			D46013P	G			YL951-YN501
0024	20		CQ		3-6	23-34-01	D48323P	11			D46013P	B04			YC054-YD158
0025	20		CQ		3-6	23-34-01	D48323P	12			D46013P	B05			YC054-YD157
0028	20		CQ		11-6	22-14-11	D46061P	28			D46013P	A10			YC051-YD158, YR301-YR328
0028	20		CQ		11-7	22-14-11	D46061P	28			D46013P	A10			YL951-YN501
0031	20		PA		13-3	SPARE	D46061P	31			D48323P	1			YC053-YD157
0031	20		PA		13-3	23-11-21	D46061P	31			D48323P	1			YD158
0031	20		PA		114-7	23-11-21	D46061P	31			D40621P	1			YL951-YL999
0031	20		PA		95-2	23-11-21	D46061P	31			D40621P	1			YN231-YN501
0031	20		PA		114-3	23-11-21	D46061P	31			D40621P	1			YR301-YR328
0032	20		PA		13-3	SPARE	D46061P	32			D48323P	2			YC053-YD157
0032	20		PA		13-3	23-11-21	D46061P	32			D48323P	2			YD158
0032	20		PA		114-7	23-11-21	D46061P	32			D40621P	2			YL951-YL999
0032	20		PA		95-2	23-11-21	D46061P	32			D40621P	2			YN231-YN501
0032	20		PA		114-3	23-11-21	D46061P	32			D40621P	2			YR301-YR328
0033	20		PA		13-3	SPARE	D46061P	33			D48323P	3			YC053-YD157
0033	20		PA		13-3	23-11-21	D46061P	33			D48323P	3			YD158
0033	20		PA		114-7	23-11-21	D46061P	33			D40621P	3			YL951-YL999
0033	20		PA		95-2	23-11-21	D46061P	33			D40621P	3			YN231-YN501
0033	20		PA		114-3	23-11-21	D46061P	33			D40621P	3			YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W2100

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY	Description Fam FT-IN Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W2103	286A2103	RIGHT AC ELEX PWR FROM P6 TO E1. (continued)									
0043	22	CQ	13-3	31-53-11	D46013P	B10	D46061P	5			YC060-YC064
0043	22	CQ	11-7	31-53-11	D46013P	B10	D46061P	20			YL953-YL999, YN233-YN501 YR301-YR328
0043	22	CQ	11-6	31-53-11	D46013P	B10	D46061P	20			
W2104	286A2104	P5 OVHD PANEL TO EE BAY (E2-2) LA1									
0001	20	CQ	7-5	33-42-11	S00261	5	C	*	D40504P	1	YC051-YC052, YC056-YC064
0001	20	CQ	7-6	33-42-11	S00261	5	C	*	D40504P	1	YC053-YC055
0001	20	CQ	7-7	33-42-11	S00261	5	C	*	D40504P	1	YC065-YD158, YL951-YR328
0002	20	CQ	0-7	33-42-11	S00261	5	C	*	S00261	2	C YC051-YD158, YL951-YR328
0003	20	CQ	29-8	33-42-11	S00261	3	C		D40506P	A01	YC051-YC052
0003	20	CQ	29-7	33-42-11	S00261	3	C		D40506P	A01	YC053-YD158, YL951-YR328
0004	20	CQ	29-8	33-42-11	S00261	4	C		D40506P	B01	YC051-YC052
0004	20	CQ	29-7	33-42-11	S00261	4	C		D40506P	B01	YC053-YD158, YL951-YR328
0005	20	CQ	29-8	33-42-11	S00261	6	C		D40506P	A02	YC051-YC052
0005	20	CQ	29-7	33-42-11	S00261	6	C		D40506P	A02	YC053-YD158, YL951-YR328
0008	20	PA	8-5	33-44-12	S00058	9	C		D40504P	5	YC051-YC052, YC065-YD158, YL951-YR328
0008	20	PA	8-9	33-44-12	S00058	9	C		D40504P	5	YC053-YC055
0008	20	PA	8-4	33-44-12	S00058	9	C		D40504P	5	YC056-YC058
0008	20	PA	8-3	33-44-12	S00058	9	C		D40504P	5	YC059-YC064
0009	20	PA	30-8	33-44-12	S00058	8	C		D40506P	B02	YC051-YC052
0009	20	PA	30-10	33-44-12	S00058	8	C		D40506P	B02	YC053-YC055
0009	20	PA	30-6	33-44-12	S00058	8	C		D40506P	B02	YC056-YC058, YC065-YD158, YL951-YR328
0009	20	PA	30-5	33-44-12	S00058	8	C		D40506P	B02	YC059-YC064
0010	18	PA	7-8	33-45-11	S00061	3	C		D40504P	10	YC051-YC052
0010	18	PA	7-9	33-45-11	S00061	3	C		D40504P	10	YC053-YC055, YC065-YD158, YL951-YR328
0010	18	PA	7-7	33-45-11	S00061	3	C		D40504P	10	YC056-YC064

WIRE LIST

D280A108

91-21-11

Section W2100

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W2104	286A2104				P5 OVHD PANEL TO EE BAY (E2-2) LA1 (continued)												
0011	16		PA		8-7	33-45-11		S00061	1	C		D40502P	4			YC051-YC052	
0011	16		PA		8-9	33-45-11		S00061	1	C		D40502P	4			YC053-YC055, YC059-YD158, YL951-YR328	
0011	16		PA		8-8	33-45-11		S00061	1	C		D40502P	4			YC056-YC058	
0012	18		PA		7-6	33-45-11		S00268	3	C		D40504P	4			YC051-YC052, YC059-YC064	
0012	18		PA		7-7	33-45-11		S00268	3	C		D40504P	4			YC053-YC055	
0012	18		PA		7-4	33-45-11		S00268	3	C		D40504P	4			YC056-YC058	
0012	18		PA		7-8	33-45-11		S00268	3	C		D40504P	4			YC065-YD158, YL951-YR328	
0013	16		PA		29-9	33-45-11		S00268	1	C		D40506P	K			YC051-YC052	
0013	16		PA		29-8	33-45-11		S00268	1	C		D40506P	K			YC053-YC055, YC059-YD158, YL951-YR328	
0013	16		PA		29-6	33-45-11		S00268	1	C		D40506P	K			YC056-YC058	
0014	20		PA		8-6	33-44-11		S00057	1	C		D40504P	6			YC051-YC052	
0014	20		PA		8-7	33-44-11		S00057	1	C		D40504P	6			YC053-YC055, YC065-YD158, YL951-YR328	
0014	20		PA		8-4	33-44-11		S00057	1	C		D40504P	6			YC056-YC058	
0014	20		PA		8-5	33-44-11		S00057	1	C		D40504P	6			YC059-YC064	
0015	20		PA		7-10	33-44-11		S00057	2	C	*	TB0501X	B026	1A		YC051-YC052	
0015	20		PA		7-9	33-44-11		S00057	2	C	*	TB0501X	B026	1A		YC053-YC055	
0015	20		PA		7-8	33-44-11		S00057	2	C	*	TB0501X	B026	1A		YC056-YC058	
0015	20		PA		8-0	33-44-11		S00057	2	C	*	TB0501X	B026	1A		YC059-YC064	
0015	20		PA		8-3	33-44-11		S00057	2	C	*	TB0501X	B026	1A		YC065-YD158, YL951-YR328	
0016	20		PA		30-8	33-44-11		S00057	2	C	*	D40506P	A03			YC051-YC052	
0016	20		PA		30-7	33-44-11		S00057	2	C	*	D40506P	A03			YC053-YC055, YC059-YD158, YL951-YR328	
0016	20		PA		30-6	33-44-11		S00057	2	C	*	D40506P	A03			YC056-YC058	
0501	20		PA		6-9	27-23-11		D00630	41			D40502P	2			YC051-YC052	
0501	20		PA		7-0	27-23-11		D00630	41			D40502P	2			YC053-YD158, YL951-YR328	
0504	22		PA		7-6	29-11-11		D02486	9			D40502P	9			YC051-YC058, YC065-YD158, YL951-YR328	

WIRE LIST

D280A108

91-21-11

Section W2100

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2104	286A2104				P5 OVHD PANEL TO EE BAY (E2-2) LA1 (continued)											
0504	22		PA		7-7	29-11-11	D02486			9		D40502P	9			YC059-YC064
0505	22		PA		28-10	29-11-11	D02486			10		D40506P	B07			YC051-YC052
0505	22		PA		28-7	29-11-11	D02486			10		D40506P	B07			YC053-YD158, YL951-YR328
0508	24		PK		6-0	29-31-11	D00630			8		TB0261X	A003	1A		YC051-YC052
0508	24		PK		6-2	29-31-11	D00630			8		TB0261X	A003	1A		YC053-YC058, YC065-YD158, YL951-YR328
0508	24		PK		6-1	29-31-11	D00630			8		TB0261X	A003	1A		YC059-YC064
0509	24		B6		20-4	29-33-11	D00642			7		D48100P	A05			YC051-YC052
0509	24		B6		20-1	29-33-11	D00642			7		D48100P	A05			YC053-YD158, YL951-YR328
0510	24		B6		28-8	29-34-11	D00642			6		D40506P	B06			YC051-YC052
0510	24		B6		28-4	29-34-11	D00642			6		D40506P	B06			YC053-YC058
0510	24		B6		28-5	29-34-11	D00642			6		D40506P	B06			YC059-YD158, YL951-YR328
0511	20		PA		19-10	27-53-11	D00624			33		D48100P	A06			YC051-YC052
0511	20		PA		19-9	27-53-11	D00624			33		D48100P	A06			YC053-YC058
0511	20		PA		19-8	27-53-11	D00624			33		D48100P	A06			YC059-YD158, YL951-YR328
0513	24		PK		6-0	29-35-11	D00624			20		TB0261X	B003	1A		YC051-YC052, YC059-YC064
0513	24		PK		6-2	29-35-11	D00624			20		TB0261X	B003	1A		YC053-YC058
0513	24		PK		6-1	29-35-11	D00624			20		TB0261X	B003	1A		YC065-YD158, YL951-YR328
0514	24		PK		28-2	27-23-14	D00624			24		D40506P	B09			YC051-YC052
0514	24		PK		28-1	27-23-14	D00624			24		D40506P	B09			YC053-YC058
0514	24		PK		27-11	27-23-14	D00624			24		D40506P	B09			YC059-YC064
0514	24		PK		28-0	27-23-14	D00624			24		D40506P	B09			YC065-YD158, YL951-YR328
0515	20		PA		6-0	27-53-11	D00624			17		TB0261X	A002	1A		YC051-YC052, YC059-YC064
0515	20		PA		6-2	27-53-11	D00624			17		TB0261X	A002	1A		YC053-YC058
0515	20		PA		6-1	27-53-11	D00624			17		TB0261X	A002	1A		YC065-YD158, YL951-YR328
0516	20		PA		6-0	27-53-11	D00624			30		TB0261X	B002	1A		YC051-YC052, YC059-YC064
0516	20		PA		6-2	27-53-11	D00624			30		TB0261X	B002	1A		YC053-YC058

WIRE LIST

D280A108

91-21-11
Section W2100
Page 8
Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W2104	286A2104				P5 OVHD PANEL TO EE BAY (E2-2) LA1 (continued)											
0516	20		PA		6-1	27-53-11		D00624		30		TB0261X	B002	1A		YC065-YD158, YL951-YR328
0517	20		PA		19-10	27-53-11		D00624		5		D48100P	A01			YC051-YC052
0517	20		PA		19-9	27-53-11		D00624		5		D48100P	A01			YC053-YC058
0517	20		PA		19-8	27-53-11		D00624		5		D48100P	A01			YC059-YD158, YL951-YR328
0518	20		PA		19-10	27-53-11		D00624		15		D48100P	A02			YC051-YC052
0518	20		PA		19-9	27-53-11		D00624		15		D48100P	A02			YC053-YC058
0518	20		PA		19-8	27-53-11		D00624		15		D48100P	A02			YC059-YD158, YL951-YR328
0520	20		PA		6-10	27-53-11		D00624		4		D40502P		8		YC051-YC052
0520	20		PA		7-0	27-53-11		D00624		4		D40502P		8		YC053-YC058
0520	20		PA		6-11	27-53-11		D00624		4		D40502P		8		YC059-YD158, YL951-YR328
0521	22		CQ		20-6	29-11-12		D02486		13		D48100P	A03			YC051-YC052
0521	22		CQ		20-3	29-11-12		D02486		13		D48100P	A03			YC053-YD158, YL951-YR328
0522	22		CQ		20-6	29-11-12		D02486		14		D48100P	A04			YC051-YC052
0522	22		CQ		20-3	29-11-12		D02486		14		D48100P	A04			YC053-YD158, YL951-YR328
5501	18		CQ		6-4	30-42-11		D11988		5		TB0505V	B031	1		YC051-YC052
5501	18		CQ		6-3	30-42-11		D11988		5		TB0505V	B031	1		YC053-YC058
5501	18		CQ		6-6	30-42-11		D11988		5		TB0505V	B031	1		YC059-YC063
5502	18		CQ		18-11	SPARE		TB0505V		B031	1	TB1806V	B013	1		YC051-YC052, YC065-YD158
5502	18		CQ		18-9	SPARE		TB0505V		B031	1	TB1806V	B013	1		YC053-YC058
5502	18		CQ		18-8	SPARE		TB0505V		B031	1	TB1806V	B013	1		YC059-YC064
5505	18		CQ		3-8	30-42-11		TB0505V		B031	1	D40504P		7		YC051-YC055
5505	18		CQ		3-7	30-42-11		TB0505V		B031	1	D40504P		7		YC056-YC058
5505	18		CQ		3-6	30-42-11		TB0505V		B031	1	D40504P		7		YC059-YC063
5505	18		CQ		6-11	30-42-11		D11988		5		D40504P		7		YC064
5505	18		CQ		7-1	30-42-11		D11988		5		D40504P		7		YC065-YD158, YL951-YR328
6007	22		CQ		24-10	26-16-21		D40504P		2		D40506P	A04			YC053-YC055, YC065-YD158, YL951-YR328
6007	22		CQ		24-8	26-16-21		D40504P		2		D40506P	A04			YC056-YC064

WIRE LIST

D280A108

91-21-11

Section W2100

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Fam	Description FT-IN Diagram		From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity	
W2104	286A2104				P5 OVHD PANEL TO EE BAY (E2-2) LA1 (continued)											
6008	22		CQ		24-10	26-16-21	D40504P		3		D40506P		B04		YC053-YC055, YC065-YD158, YL951-YR328	
6008	22		CQ		24-8	26-16-21	D40504P		3		D40506P		B04		YC056-YC064	
6009	22		CQ		24-10	26-16-22	D40504P		8		D40506P		A06		YC053-YC055, YC065-YD158, YL951-YR328	
6009	22		CQ		24-8	26-16-22	D40504P		8		D40506P		A06		YC056-YC064	
6010	22		CQ		24-10	26-16-22	D40504P		9		D40506P		A07		YC053-YC055, YC065-YD158, YL951-YR328	
6010	22		CQ		24-8	26-16-22	D40504P		9		D40506P		A07		YC056-YC064	
6011	22		CQ		24-10	26-23-11	D40504P		11		D40506P		A08		YC053-YC055, YC065-YD158, YL951-YR328	
6011	22		CQ		24-8	26-23-11	D40504P		11		D40506P		A08		YC056-YC064	
6012	22		CQ		24-10	SPARE	D40504P		12		D40506P		A09		YC053-YC055, YC065-YD157, YL951-YR314, YR317-YR318, YR320-YR328	
6012	22		CQ		24-8	SPARE	D40504P		12		D40506P		A09		YC056-YC064	
6012	22		CQ		24-10	26-23-11	D40504P		12		D40506P		A09		YD158, YR315-YR316, YR319	
W2108	286A2108				WINDSHIELD HEAT DISCONNECT TO E2-1 (LA1)											
1001	18	X1	AA		28-10	30-41-11	A00006		3	E	*	D40070P		F		YC051-YC055
1001	18	X1	AA		28-8	30-41-11	A00006		3	E	*	D40070P		F		YC056-YN236, YN501-YR319
1001	18	X1	AA		28-1	30-41-11	A00006		3	E	*	D40070P		F		YN237-YN260, YR320-YR328
1001Z			AA		0-0	30-41-11	A00006				AC	D40070P	PERG	1F		ALL
1002	18	X1	AB		3-4	30-41-11	A00006		3	E	*	A00006	4	E		ALL
1002Z			AB		0-0	30-41-11	A00006	DED				A00006	DED			ALL
1003	20	X1	AC		2-6	30-41-11	D10564		3			GD01352	AC..	E		YC051-YC063
1003	20	X1	AC		2-6	30-41-11	D10564		3			GD01352	AC..	E	*	YC064-YR328
1003Z			AC		0-0	30-41-11	D10564				AB	GD01352	AC..	E		YC051-YC063
1003Z			AC		0-0	30-41-11	D10564				AB	GD01352	AC..	E	*	YC064-YR328
1004	20	X1	AD		35-1	30-41-11	D10564		4			D40070P	A03			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W2100

Page 10

Nov 12/2012

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To					
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W2108	286A2108			WINDSHIELD HEAT DISCONNECT TO E2-1 (LA1) (continued)											
1004	20	X1	AD	35-0	30-41-11	D10564	4			D40070P	A03			YC056-YN236, YN501-YR319	
1004	20	X1	AD	34-4	30-41-11	D10564	4			D40070P	A03			YN237-YN260, YR320-YR328	
1004Z			AD	0-0	30-41-11	D10564			AB	D40070P	PERG	1F		ALL	
2001B	20	X2	GA	35-1	30-41-11	D10564	2			D40070P	A08			YC051-YC055	
2001B	20	X2	GA	35-0	30-41-11	D10564	2			D40070P	A08			YC056-YN236, YN501-YR319	
2001B	20	X2	GA	34-4	30-41-11	D10564	2			D40070P	A08			YN237-YN260, YR320-YR328	
2001R	20	X2	GA	0-0	30-41-11	D10564	1			D40070P	A07			ALL	
2001Z			GA	0-0	30-41-11	D10564			AB	D40070P	PERG	1F		ALL	
2002B	20	X2	GB	41-8	30-41-11	A00006	=D	C		S01078	4	C		YC051-YC055	
2002B	20	X2	GB	41-9	30-41-11	A00006	=D	C		S01078	4	C		YC056-YN236, YN501-YR319	
2002B	20	X2	GB	41-11	30-41-11	A00006	=D	C		S01078	4	C		YN237-YN260, YR320-YR322	
2002B	20	X2	GB	41-3	30-41-11	A00006	=D	C		S01078	4	C		YR323-YR328	
2002R	20	X2	GB	0-0	30-41-11	A00006	=C	C		S01078	1	C		ALL	
2002Z			GB	0-0	30-41-11	A00006			AC	S01078			AD	ALL	
2003B	20	X2	GC	41-11	30-41-11	A00006	=A	C		S01078	6	C		YC051-YC055	
2003B	20	X2	GC	42-0	30-41-11	A00006	=A	C		S01078	6	C		YC056-YN236, YN501-YR319	
2003B	20	X2	GC	42-3	30-41-11	A00006	=A	C		S01078	6	C		YN237-YN260, YR320-YR322	
2003B	20	X2	GC	41-6	30-41-11	A00006	=A	C		S01078	6	C		YR323-YR328	
2003R	20	X2	GC	0-0	30-41-11	A00006	=B	C		S01078	3	C		ALL	
2003Z			GC	0-0	30-41-11	A00006			AC	S01078			AD	ALL	
2004B	20	X2	GD	19-5	30-41-11	S01078	5	C		D40070P	A06			YC051-YC055	
2004B	20	X2	GD	19-10	30-41-11	S01078	5	C		D40070P	A06			YC056-YR322	
2004B	20	X2	GD	19-9	30-41-11	S01078	5	C		D40070P	A06			YR323-YR328	
2004R	20	X2	GD	0-0	30-41-11	S01078	2	C		D40070P	A05			ALL	
2004Z			GD	0-0	30-41-11	S01078	DED			D40070P	PERG	1F		ALL	
5501	18	PA		2-0	30-42-11	GD00102	DC..	E		D00062	1			YC051-YC063	
5501	16	PA		2-0	30-42-11	GD00102	DC..	E		D00062	1			YC064-YR328	
5502	18	GA		21-9	30-42-11	TB1806V	B013	1		D00062	2			YC051-YC055	
5502	18	PA		21-9	30-42-11	TB1806V	B013	1		D00062	2			YC056-YC061	
5502	18	PA		17-8	30-42-11	SP01084		9		D00062	2			YC062-YC063	
5502	14	PA		1-0	30-42-11	SM00001		9		D00062	2	14		YC064-YR328	

WIRE LIST

D280A108

91-21-11

Section W2100

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2108		286A2108			WINDSHIELD HEAT DISCONNECT TO E2-1 (LA1) (continued)											
5503		24		PK		21-9	30-42-11	TB1806X	B008	1A		D00062	3			ALL
5504		10		PA		17-2	30-42-11	SP01084		9		SM00001		9		YC064-YR328
FRAB						0-0	30-41-11	D10564		5		D10564			AB	ALL
FRAC						0-0	30-41-11	A00006			AC	GD00977	ST..	E		ALL
FRAD						0-0	30-41-11	S01078			AD	GD00568	ST..	E		ALL

WIRE LIST

D280A108

91-21-11

Section W2100

Page 12 End

Nov 12/2012



WIRE LIST

91-21-11

Section W2110

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To					
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W2110	286A2110				CARGO SMOKE DETECTION & FIRE SUPPRESSION MODULE (P8-75) E2-2 SHELF (continued)											
6020	22		PA		27-1	26-16-22	D12760		37			D46022P	B06			YC053-YC055
6020	22		PA		27-4	26-16-22	D12760		37			D46022P	B06			YC056-YR328
6021	22		CQ		27-1	26-16-22	D12760		38			D46022P	B07			YC053-YC055
6021	22		CQ		27-4	26-16-22	D12760		38			D46022P	B07			YC056-YR328
6022	22		PA		27-0	26-23-11	D12760		48			D40646P	A06			YC053-YC055
6022	22		PA		27-3	26-23-11	D12760		48			D40646P	A06			YC056-YR328
6023	22		PA		27-0	26-23-11	D12760		45			D40646P	A07			YC053-YC055
6023	22		PA		27-3	26-23-11	D12760		45			D40646P	A07			YC056-YD157, YL951-YR314, YR317-YR318, YR320-YR328
6024	22		PA		27-0	26-23-11	D12760		28			D40646P	A01			YC053-YC055
6024	22		PA		27-3	26-23-11	D12760		28			D40646P	A01			YC056-YD157, YL951-YR314, YR317-YR318, YR320-YR328
6025	22		CQ		27-0	26-23-11	D12760		26			D40646P	A03			YC053-YC055
6025	22		CQ		27-3	26-23-11	D12760		26			D40646P	A03			YC056-YD157, YL951-YR314, YR317-YR318, YR320-YR328
6026	22		CQ		27-0	26-23-11	D12760		24			D40646P	A05			YC053-YC055
6026	22		CQ		27-3	26-23-11	D12760		24			D40646P	A05			YC056-YD157, YL951-YR314, YR317-YR318, YR320-YR328
6027	20		PA		4-8	26-23-11	D12760		12			GD00807	DC..	1A		YC053-YD157, YL951-YR314, YR317-YR318, YR320-YR328
6028	20		PA		4-8	26-23-11	D12760		23			GD00807	DC..	1A		YC053-YD157, YL951-YR314, YR317-YR318, YR320-YR328
6029	20		PA		5-3	33-18-64	D12760		60			TB0804Z	A017	1A		YC053-YR328
6030	20		PA		4-11	33-18-64	D12760		55			TB0804Y	A007	1A		YC053-YR328
6032	20		CQ		4-8	33-11-33	D12760		2			TB0801W	A005	1		YC053-YR328
6033	20		CQ		4-8	33-11-33	D12760		1			GD00807	AC..	1A		YC053-YR328
6034	22		CQ		27-0	26-16-21	D12760		49			D40646P	B07			YC053-YC055

WIRE LIST

D280A108

91-21-11

Section W2110

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2110		286A2110					CARGO SMOKE DETECTION & FIRE SUPPRESSION MODULE (P8-75) E2-2 SHELF (continued)								
	6034	22	CQ		27-3	26-16-21	D12760	49			D40646P	B07			YC056-YC065
	6034	22	PA		27-3	26-16-21	D12760	49			D40646P	B07			YC067-YR328
	6035	22	CQ		27-0	26-11-21	D12760	56			D40646P	B08			YC053-YC055
	6035	22	CQ		27-3	26-11-21	D12760	56			D40646P	B08			YC056-YC065
	6035	22	PA		27-3	26-11-21	D12760	56			D40646P	B08			YC067-YR328
	6036	22	CQ		27-0	26-11-31	D12760	34			D40646P	B09			YC053-YC055
	6036	22	CQ		27-3	26-11-31	D12760	34			D40646P	B09			YC056-YR328
	6037	22	CQ		27-4	26-23-11	D12760	12			D46022P	A01			YD158-YD170,
															YR315-YR316, YR319
	6038	22	CQ		27-4	26-23-11	D12760	23			D46022P	A03			YD158-YD170,
															YR315-YR316, YR319
	6039	22	CQ		27-3	26-23-11	D12760	45			D40646P	A05			YD158-YD170,
															YR315-YR316, YR319
	6040	22	CQ		27-3	26-23-11	D12760	28			D40646P	A07			YD158-YD170,
															YR315-YR316, YR319
	6041	22	CQ		27-3	26-23-11	D12760	26			D40646P	A01			YD158-YD170,
															YR315-YR316, YR319
	6042	22	CQ		27-3	26-23-11	D12760	24			D40646P	A03			YD158-YD170,
															YR315-YR316, YR319
	6043	22	CQ		4-7	26-23-11	D12760	16			TB0801X	A002	1A		YD158-YD170,
															YR315-YR316, YR319
	6043	22	CQ		4-7	SPARE	D12760	CAP Y			TB0801X	A002	1A		YR317
	6044	24	PK		27-0	31-31-15	D40646P	A02			D12760	58			YC053-YC055
	6044	24	PK		27-3	31-31-15	D40646P	A02			D12760	58			YC056-YC059,
															YC065-YD158
	6044	24	PK		27-3	31-31-15	SP00479		9		D12760	58			YC060-YC064
	6044	24	PK		27-3	26-16-21	D40646P	A02			D12760	58			YL951-YR328
	6045	24	PK		27-0	31-31-15	D40646P	B10			D12760	50			YC053-YC055
	6045	24	PK		27-3	31-31-15	D40646P	B10			D12760	50			YC056-YC059,
															YC065-YD158
	6045	24	PK		27-3	31-31-15	SP00481		9		D12760	50			YC060-YC064
	6045	24	PK		27-3	26-16-22	D40646P	B10			D12760	50			YL951-YR328
W2112		286A2112					P5 OVHD PANEL TO EE BAY (E2-1/E2-2/E3-1) LA2								
	0001	20	PA		7-10	33-49-11	D40514P	11			S00635	2	C		YC053-YC055
	0001	20	PA		8-6	33-49-11	D40514P	11			S00635	2	C		YC056-YC058
	0001	20	PA		8-2	33-49-11	D40514P	11			S00635	2	C		YC059-YC064
	0001	20	PA		8-3	33-49-11	D40514P	11			S00635	2	C		YC065-YR328
	0002	20	PA		37-2	33-49-11	S00635	1	C		D40596P	A01			YC053-YC055

WIRE LIST

D280A108

91-21-11

Section W2110

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity			
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice	
W2112	286A2112				P5 OVHD PANEL TO EE BAY (E2-1/E2-2/E3-1) LA2 (continued)											
0002	20	PA		38-0	33-49-11	S00635		1	C		D40596P	A01			YC056-YC058	
0002	20	PA		37-8	33-49-11	S00635		1	C		D40596P	A01			YC059-YC064	
0002	20	PA		37-9	33-49-11	S00635		1	C		D40596P	A01			YC065-YR328	
0003	20	PA		32-7	33-25-11	TB0504X		B016	1A		D40596P	A02			YC053-YC055	
0003	20	PA		33-1	33-25-11	TB0504X		B016	1A		D40596P	A02			YC056-YC058, YC065-YR328	
0003	20	PA		33-0	33-25-11	TB0504X		B016	1A		D40596P	A02			YC059-YC064	
0004	20	PA		31-2	33-43-11	S00058		5	C		D40520P	B18			YC053-YC064	
0004	20	PA		31-3	33-43-11	S00058		5	C		D40520P	B18			YC065-YR328	
0005	20	PA		8-0	33-43-11	S00058		6	C	*	D40514P	10			YC053-YC055	
0005	20	PA		8-4	33-43-11	S00058		6	C	*	D40514P	10			YC056-YC064	
0005	20	PA		8-5	33-43-11	S00058		6	C	*	D40514P	10			YC065-YR328	
0006	20	PA		2-4	33-43-11	S00058		6	C	*	S00058	4	C		YC053-YC064	
0006	20	PA		1-6	33-43-11	S00058		6	C	*	S00058	4	C		YC065-YR328	
0062	22	PA		14-11	33-22-11	D00652		14			SP00897		S		YN501-YR328	
0063	22	PA		14-11	33-22-11	D00652		5			SP00899		S		YN501-YR328	
0501	22	PA		28-8	24-11-11	D01086		20			D40598P	B10			YC053-YC055, YC059-YC064	
0501	22	PA		28-9	24-11-11	D01086		20			D40598P	B10			YC056-YC058, YC065-YR328	
0502	20	PA		2-7	24-11-11	D01086		37			GD00517	DC..	1A		YC053-YC064	
0502	20	PA		2-8	24-11-11	D01086		37			GD00517	DC..	1A		YC065-YR328	
0503	22	PA		21-5	24-22-11	D00722		20			D48102P	A03			YC053-YC058	
0503	22	PA		21-6	24-22-11	D00722		20			D48102P	A03			YC059-YR328	
0504	22	PA		29-5	24-22-11	D00722		4			D40598P	B04			YC053-YC055	
0504	22	PA		29-6	24-22-11	D00722		4			D40598P	B04			YC056-YC058	
0504	22	PA		29-7	24-22-11	D00722		4			D40598P	B04			YC059-YR328	
0505	22	PA		5-4	24-22-11	D00722		21			TB0505Y	A003	1A		YC053-YC058	
0505	22	PA		6-2	24-22-11	D00722		21			TB0505Y	A003	1A		YC059-YC064	
0505	22	PA		6-3	24-22-11	D00722		21			TB0505Y	A003	1A		YC065-YR328	
0506	22	PA		26-4	24-22-11	TB0505Y		A003	1A		D40598P	A05			YC053-YC055, YC059-YC064	
0506	22	PA		26-5	24-22-11	TB0505Y		A003	1A		D40598P	A05			YC056-YC058	
0506	22	PA		26-3	24-22-11	TB0505Y		A003	1A		D40598P	A05			YC065-YR328	
0510	24	PK		20-3	24-33-11	D00652		21			D48102P	A04			YC053-YC058	
0510	24	PK		20-5	24-33-11	D00652		21			D48102P	A04			YC059-YR328	
0513	20	PA		2-3	24-28-11	D00652		39			GD00515	DC..	1A		YC053-YC058	
0513	20	PA		2-4	24-28-11	D00652		39			GD00515	DC..	1A		YC059-YR328	
0514	20	PA		2-2	24-28-11	D00652		55			GD00517	ST..	1A		YC053-YC058	

WIRE LIST

D280A108

91-21-11

Section W2110

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2112	286A2112	P5 OVHD PANEL TO EE BAY (E2-1/E2-2/E3-1) LA2 (continued)													
	0514	20	PA		2-4	24-28-11	D00652		55		GD00517	ST..	1A		YC059-YR328
	0515	20	PA		2-2	24-28-11	D00652		24		GD00517	DC..	1A		YC053-YC058
	0515	20	PA		2-4	24-28-11	D00652		24		GD00517	DC..	1A		YC059-YR328
	0517	20	PA		20-11	27-53-12	D00624		16		TB1808X	B004	1A		YC053-YC058
	0517	20	PA		20-10	27-53-12	D00624		16		TB1808X	B004	1A		YC059-YR328
	0518	20	PA		20-11	27-53-12	D00624		6		TB1808X	A004	1A		YC053-YC058
	0518	20	PA		20-10	27-53-12	D00624		6		TB1808X	A004	1A		YC059-YR328
	0519	22	CQ		34-11	27-83-11	D00624		28		D40596P	B02			YC053-YC055
	0519	22	CQ		35-5	27-83-11	D00624		28		D40596P	B02			YC056-YC058
	0519	22	CQ		35-4	27-83-11	D00624		28		D40596P	B02			YC059-YR328
	0520	20	CQ		2-4	27-83-11	D00624		29		GD00517	DC..	1A		YC053-YR328
	0521	24	PK		6-5	27-23-14	D00630		10		TB0262X	B002	1A		YC053-YC064
	0521	24	PK		6-7	27-23-14	D00630		10		TB0262X	B002	1A		YC065-YR328
	0524	24	PK		6-6	27-31-37	TB0261X	A013	1A		D00630	20			YC053-YC064
	0524	24	PK		6-7	27-31-37	TB0261X	A013	1A		D00630	20			YC065-YR328
	1001	20	X1	AA	29-4	21-31-22	D10724		27		D40520P	A06			YC053-YC055
	1001	20	X1	AA	29-7	21-31-22	D10724		27		D40520P	A06			YC056-YC058
	1001	20	X1	AA	29-8	21-31-22	D10724		27		D40520P	A06			YC059-YR328
	1001Z			AA	0-0	21-31-22	D10724			AA	D40520P	PERG	1F		YC053-YR328
	1002	20	X1	AB	29-4	21-31-22	D10724		26		D40520P	B06			YC053-YC055
	1002	20	X1	AB	29-7	21-31-22	D10724		26		D40520P	B06			YC056-YC058
	1002	20	X1	AB	29-8	21-31-22	D10724		26		D40520P	B06			YC059-YR328
	1002Z			AB	0-0	21-31-22	D10724			AA	D40520P	PERG	1F		YC053-YR328
	1301	24	Y1	EN	19-6	73-21-12	D02952		10		D48102P	A10			YC053-YC058
	1301	24	Y1	EN	19-5	73-21-12	D02952		10		D48102P	A10			YC059-YC064
	1301	24	Y1	EN	19-4	73-21-12	D02952		10		D48102P	A10			YC065-YR328
	1301Z			EN	0-0	73-21-12	D02952			AC	D48102P	PERG	1F		YC053-YR328
	2001B	24	Y2	GA	29-4	21-31-22	D10724		21		D40520P	B08			YC053-YC055
	2001B	24	Y2	GA	29-7	21-31-22	D10724		21		D40520P	B08			YC056-YC058
	2001B	24	Y2	GA	29-8	21-31-22	D10724		21		D40520P	B08			YC059-YR328
	2001R	24	Y2	GA	0-0	21-31-22	D10724		20		D40520P	A08			YC053-YR328
	2001Z			GA	0-0	21-31-22	D10724			AA	D40520P	PERG	1F		YC053-YR328
	2002B	24	Y2	GB	29-4	21-31-22	D10724		22		D40520P	B07			YC053-YC055
	2002B	24	Y2	GB	29-7	21-31-22	D10724		22		D40520P	B07			YC056-YC058
	2002B	24	Y2	GB	29-8	21-31-22	D10724		22		D40520P	B07			YC059-YR328
	2002R	24	Y2	GB	0-0	21-31-22	D10724		9		D40520P	A07			YC053-YR328
	2002Z			GB	0-0	21-31-22	D10724			AA	D40520P	PERG	1F		YC053-YR328
	2003B	24	Y2	GC	29-3	30-41-11	D00638		4		D40518P	B02			YC053-YC055
	2003B	24	Y2	GC	29-4	30-41-11	D00638		4		D40518P	B02			YC056-YC058

WIRE LIST

D280A108

91-21-11

Section W2110

Page 5

Nov 12/2012



WIRE LIST
D280A108

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W2112	286A2112				P5 OVHD PANEL TO EE BAY (E2-1/E2-2/E3-1) LA2 (continued)											
5505	22		CQ		21-11	21-27-21		S00059		2	C	D48102P	A01			YC053-YC055, YC059-YC064
5505	22		CQ		21-9	21-27-21		S00059		2	C	D48102P	A01			YC056-YC058
5505	22		CQ		22-0	21-27-21		S00059		2	C	D48102P	A01			YC065-YR328
5506	22		CQ		7-8	21-27-21		S00059		3	C	GD00516	DC..	1A		YC053-YC055, YC059-YC064
5506	22		CQ		7-5	21-27-21		S00059		3	C	GD00516	DC..	1A		YC056-YC058
5506	22		CQ		7-6	21-27-21		S00059		3	C	GD00516	DC..	1A		YC065-YR328
5508	22		PA		34-6	30-31-11		D00644		40		D40596P	B04			YC053-YC055
5508	22		PA		35-0	30-31-11		D00644		40		D40596P	B04			YC056-YC058
5508	22		PA		35-2	30-31-11		D00644		40		D40596P	B04			YC059-YR328
5510	24		B6		26-7	21-31-11		TB0505Y	B013	1A		D40520P	A03			YC053-YC055, YC059-YC064
5510	24		B6		26-8	21-31-11		TB0505Y	B013	1A		D40520P	A03			YC056-YC058
5510	24		B6		26-10	21-31-11		TB0505Y	B013	1A		D40520P	A03			YC065-YR328
5511	20		CQ		5-2	21-31-22		D10726		20		TB0505Y	B015	1A		YC053-YC058
5511	20		CQ		6-0	21-31-22		D10726		20		TB0505Y	B015	1A		YC059-YC064
5511	20		CQ		6-4	21-31-22		D10726		20		TB0505Y	B015	1A		YC065-YR328
5512	20		PA		3-2	21-31-22		D10726		21		GD00516	DC..	1A		YC053-YC058
5512	20		PA		3-3	21-31-22		D10726		21		GD00516	DC..	1A		YC059-YR328
5514	20		PA		3-0	21-31-22		D10724		11		GD00516	ST..	1A		YC053-YC055
5514	20		PA		3-2	21-31-22		D10724		11		GD00516	ST..	1A		YC056-YC064
5514	20		PA		3-3	21-31-22		D10724		11		GD00516	ST..	1A		YC065-YR328
5515	20		PA		3-0	21-31-22		D10724		12		GD00516	ST..	1A		YC053-YC055
5515	20		PA		3-2	21-31-22		D10724		12		GD00516	ST..	1A		YC056-YC064
5515	20		PA		3-3	21-31-22		D10724		12		GD00516	ST..	1A		YC065-YR328
5516	24		B6		29-4	21-31-22		D10724		4		D40520P	B03			YC053-YC055
5516	24		B6		29-7	21-31-22		D10724		4		D40520P	B03			YC056-YC058
5516	24		B6		29-8	21-31-22		D10724		4		D40520P	B03			YC059-YR328
5517	24		B6		5-0	21-31-22		D10724		5		TB0505Y	A015	1A		YC053-YC055
5517	24		B6		5-2	21-31-22		D10724		5		TB0505Y	A015	1A		YC056-YC058
5517	24		B6		6-0	21-31-22		D10724		5		TB0505Y	A015	1A		YC059-YC064
5517	24		B6		6-4	21-31-22		D10724		5		TB0505Y	A015	1A		YC065-YR328
5518	24		B6		2-4	21-31-22		D10724		2		D00680	17			YC053-YC055
5518	24		B6		2-7	21-31-22		D10724		2		D00680	17			YC056-YR328
5519	24		B6		4-3	21-31-22		D00646		14		TB0505Y	A015	1A		YC053-YC058
5519	24		B6		4-7	21-31-22		D00646		14		TB0505Y	A015	1A		YC059-YC064
5519	24		B6		4-11	21-31-22		D00646		14		TB0505Y	A015	1A		YC065-YR328
5520	24		PK		28-7	21-31-22		D00646		7		D40520P	A02			YC053-YC055

WIRE LIST

D280A108

91-21-11

Section W2110

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W2112	286A2112				P5 OVHD PANEL TO EE BAY (E2-1/E2-2/E3-1) LA2 (continued)											
5520	24		PK		28-8	21-31-22		D00646		7		D40520P	A02		YC056-YC058	
5520	24		PK		28-9	21-31-22		D00646		7		D40520P	A02		YC059-YR328	
5521	24		B6		4-5	21-31-22		D40512P		1		TB0505Y	A015	1A	YC053-YC064	
5521	24		B6		4-7	21-31-22		D40512P		1		TB0505Y	A015	1A	YC065-YR328	
5522	20		CQ		4-5	21-31-22		D40512P		11		TB0505Y	B015	1A	YC053-YC064	
5522	20		CQ		4-7	21-31-22		D40512P		11		TB0505Y	B015	1A	YC065-YR328	
5523	20		CQ		26-7	21-31-22		TB0505Y		B015	1A	D40520P	A12		YC053-YC055, YC059-YC064	
5523	20		CQ		26-8	21-31-22		TB0505Y		B015	1A	D40520P	A12		YC056-YC058	
5523	20		CQ		26-10	21-31-22		TB0505Y		B015	1A	D40520P	A12		YC065-YR328	
5524	24		B6		27-3	21-31-22		D40512P		8		D40520P	A05		YC053-YC058	
5524	24		B6		27-4	21-31-22		D40512P		8		D40520P	A05		YC059-YR328	
5525	22		CQ		6-6	30-31-12		D00638		33		D40512P	9		YC053-YC058	
5525	22		CQ		6-8	30-31-12		D00638		33		D40512P	9		YC059-YR328	
5526	22		CQ		4-7	30-31-12		D00638		39		D40514P	24		YC053-YC055	
5526	22		CQ		4-11	30-31-12		D00638		39		D40514P	24		YC056-YC058	
5526	22		CQ		5-0	30-31-12		D00638		39		D40514P	24		YC059-YR328	
5527	22		CQ		4-7	30-31-12		D00638		46		D40514P	12		YC053-YC055	
5527	22		CQ		4-11	30-31-12		D00638		46		D40514P	12		YC056-YC058	
5527	22		CQ		5-0	30-31-12		D00638		46		D40514P	12		YC059-YR328	
5528	22		CQ		4-7	30-31-12		D00638		42		D40514P	13		YC053-YC055	
5528	22		CQ		4-11	30-31-12		D00638		42		D40514P	13		YC056-YC058	
5528	22		CQ		5-0	30-31-12		D00638		42		D40514P	13		YC059-YR328	
5529	22		CQ		4-7	30-31-12		D00638		43		D40514P	14		YC053-YC055	
5529	22		CQ		4-11	30-31-12		D00638		43		D40514P	14		YC056-YC058	
5529	22		CQ		5-0	30-31-12		D00638		43		D40514P	14		YC059-YR328	
5531	24		B6		4-7	30-41-11		D00638		50		D40514P	15		YC053-YC055	
5531	24		B6		4-11	30-41-11		D00638		50		D40514P	15		YC056-YC058	
5531	24		B6		5-0	30-41-11		D00638		50		D40514P	15		YC059-YR328	
5532	24		B6		29-3	30-41-11		D00638		47		D40518P	B16		YC053-YC055	
5532	24		B6		29-4	30-41-11		D00638		47		D40518P	B16		YC056-YC058	
5532	24		B6		29-5	30-41-11		D00638		47		D40518P	B16		YC059-YR328	
5533	24		B6		29-3	30-41-11		D00638		7		D40518P	B05		YC053-YC055	
5533	24		B6		29-4	30-41-11		D00638		7		D40518P	B05		YC056-YC058	
5533	24		B6		29-5	30-41-11		D00638		7		D40518P	B05		YC059-YR328	
5534	24		B6		29-3	30-41-11		D00638		6		D40518P	A06		YC053-YC055	
5534	24		B6		29-4	30-41-11		D00638		6		D40518P	A06		YC056-YC058	
5534	24		B6		29-5	30-41-11		D00638		6		D40518P	A06		YC059-YR328	
5535	24		B6		29-3	30-41-11		D00638		8		D40518P	B06		YC053-YC055	

WIRE LIST

D280A108

91-21-11

Section W2110

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2112		286A2112			P5 OVHD PANEL TO EE BAY (E2-1/E2-2/E3-1) LA2 (continued)											
5535		24		B6		29-4	30-41-11	D00638			8	D40518P		B06		YC056-YC058
5535		24		B6		29-5	30-41-11	D00638			8	D40518P		B06		YC059-YR328
5536		24		B6		4-7	30-41-11	D00638			51	D40514P		16		YC053-YC055
5536		24		B6		4-11	30-41-11	D00638			51	D40514P		16		YC056-YC058
5536		24		B6		5-0	30-41-11	D00638			51	D40514P		16		YC059-YR328
5537		24		B6		6-6	30-41-11	D00638			52	D40512P		6		YC053-YC055
5537		20		CQ		6-6	30-41-11	D00638			52	D40512P		6		YC056-YC058
5537		20		CQ		6-8	30-41-11	D00638			52	D40512P		6		YC059-YR328
5538		24		B6		29-3	30-41-11	D00638			48	D40518P		A17		YC053-YC055
5538		24		B6		29-4	30-41-11	D00638			48	D40518P		A17		YC056-YC058
5538		24		B6		29-5	30-41-11	D00638			48	D40518P		A17		YC059-YR328
5539		24		B6		29-3	30-41-11	D00638			1	D40518P		B10		YC053-YC055
5539		24		B6		29-4	30-41-11	D00638			1	D40518P		B10		YC056-YC058
5539		24		B6		29-5	30-41-11	D00638			1	D40518P		B10		YC059-YR328
5540		24		B6		29-3	30-41-11	D00638			2	D40518P		A07		YC053-YC055
5540		24		B6		29-4	30-41-11	D00638			2	D40518P		A07		YC056-YC058
5540		24		B6		29-5	30-41-11	D00638			2	D40518P		A07		YC059-YR328
5541		24		B6		29-3	30-41-11	D00638			9	D40518P		B07		YC053-YC055
5541		24		B6		29-4	30-41-11	D00638			9	D40518P		B07		YC056-YC058
5541		24		B6		29-5	30-41-11	D00638			9	D40518P		B07		YC059-YR328
5542		20		CQ		1-10	30-41-11	D00638			58	GD00516		ST.. 1A		YC053-YC064
5542		20		CQ		1-11	30-41-11	D00638			58	GD00516		ST.. 1A		YC065-YR328
5544		24		B6		29-1	36-21-11	D00096			3	D40520P		A16		YC053-YC058
5544		24		B6		29-5	36-21-11	D00096			3	D40520P		A16		YC059-YC064
5544		24		B6		29-4	36-21-11	D00096			3	D40520P		A16		YC065-YR328
5545		24		B6		26-8	36-21-11	TB0506Y	A005	1A		D40520P		B16		YC053-YC055, YC059-YC064, YC056-YC058, YC065-YR328
5545		24		B6		26-9	36-21-11	TB0506Y	A005	1A		D40520P		B16		YC053-YC055, YC059-YC064, YC056-YC058, YC065-YR328
5548		22		PA		34-5	30-31-12	D00638			40	D40596P		A06		YC053-YC055
5548		22		PA		34-11	30-31-12	D00638			40	D40596P		A06		YC056-YC058
5548		22		PA		35-0	30-31-12	D00638			40	D40596P		A06		YC059-YR328
5552		20		PA		19-5	33-17-11	D40512P			14	TB1806X	B007	1A		YC053-YC058
5552		20		PA		19-6	33-17-11	D40512P			14	TB1806X	B007	1A		YC059-YR328
5553		20		PA		5-4	30-41-11	D00638			49	TB0262X	B004	1A		YC053-YC058
5553		20		PA		6-0	30-41-11	D00638			49	TB0262X	B004	1A		YC059-YC064
5553		20		PA		6-2	30-41-11	D00638			49	TB0262X	B004	1A		YC065-YR328
5555		24		B6		22-0	30-42-11	D11988			3	TB1806X	B008	1A		YC053-YR328
5556		18		CQ		3-6	30-42-11	D11988			4	GD00510	DC..	1		YC053-YC058

WIRE LIST

D280A108

91-21-11

Section W2110

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W2112	286A2112				P5 OVHD PANEL TO EE BAY (E2-1/E2-2/E3-1) LA2 (continued)											
5556	18		CQ		3-8	30-42-11	D11988		4			GD00510	DC..	1		YC059-YC064
5556	18		CQ		3-7	30-42-11	D11988		4			GD00510	DC..	1		YC065-YR328
5557	20		CQ		4-9	36-21-11	D00096		4			TB0506Y	A005	1A		YC053-YC058
5557	20		CQ		5-4	36-21-11	D00096		4			TB0506Y	A005	1A		YC059-YC064
5557	20		CQ		5-5	36-21-11	D00096		4			TB0506Y	A005	1A		YC065-YR328
5558	20		CQ		7-4	36-21-11	GD00501		DC..	1A		TB0506Y	A005	1A		YC053-YC058
5558	20		CQ		7-6	36-21-11	GD00501		DC..	1A		TB0506Y	A005	1A		YC059-YC064
5558	20		CQ		7-9	36-21-11	GD00501		DC..	1A		TB0506Y	A005	1A		YC065-YR328
5559	22		PA		4-6	23-71-01	D11125		1			D40514P	20			YC053-YC055
5559	22		PA		4-10	23-71-01	D11125		1			D40514P	20			YC056-YC058
5559	22		PA		4-11	23-71-01	D11125		1			D40514P	20			YC059-YC064
5559	22		PA		5-0	23-71-01	D11125		1			D40514P	20			YC065-YR328
5560	22		PA		4-6	23-71-01	D11125		4			D40514P	3			YC053-YC055
5560	22		PA		4-10	23-71-01	D11125		4			D40514P	3			YC056-YC058
5560	22		PA		4-11	23-71-01	D11125		4			D40514P	3			YC059-YC064
5560	22		PA		5-0	23-71-01	D11125		4			D40514P	3			YC065-YR328
5561	22		PA		29-3	23-71-01	D11125		3			D40518P	A11			YC053-YC058
5561	22		PA		29-4	23-71-01	D11125		3			D40518P	A11			YC059-YR328
5562	22		PA		29-3	23-71-01	D11125		5			D40518P	A14			YC053-YC058
5562	22		PA		29-4	23-71-01	D11125		5			D40518P	A14			YC059-YR328
5563	20		PA		3-11	33-12-11	D11125		9			TB0502V	B005	1		YC053-YC058
5563	20		PA		4-3	33-12-11	D11125		9			TB0502V	B005	1		YC059-YC064
5563	20		PA		4-7	33-12-11	D11125		9			TB0502V	B005	1		YC065-YR328
5564	20		PA		2-0	33-12-11	D11125		10			GD00520	AC..	1A		YC053-YC058
5564	20		PA		1-11	33-12-11	D11125		10			GD00520	AC..	1A		YC059-YR328
6001	22		PA		5-1	30-21-11	D00462		22			D40514P	9			YC053-YC055
6001	22		PA		6-1	30-21-11	D00462		22			D40514P	9			YC056-YR328
6002	24		PK		4-1	34-61-17	D00462		5			TB0504X	B014	1A		YC053-YC055
6002	24		PK		4-3	34-61-17	D00462		5			TB0504X	B014	1A		YC056-YC058
6002	24		PK		4-5	34-61-17	D00462		5			TB0504X	B014	1A		YC059-YC064
6002	24		PK		4-9	34-61-17	D00462		5			TB0504X	B014	1A		YC065-YR328
6003	20		PA		2-4	34-61-17	D00462		9			GD00516	DC..	1A		YC053-YC055
6003	20		PA		2-6	34-61-17	D00462		9			GD00516	DC..	1A		YC056-YC058, YC065-YR328
6003	20		PA		2-5	34-61-17	D00462		9			GD00516	DC..	1A		YC059-YC064
6004	24		PK		4-1	34-61-17	D00462		6			TB0504X	B015	1A		YC053-YC055
6004	24		PK		4-3	34-61-17	D00462		6			TB0504X	B015	1A		YC056-YC058
6004	24		PK		4-5	34-61-17	D00462		6			TB0504X	B015	1A		YC059-YC064
6004	24		PK		4-9	34-61-17	D00462		6			TB0504X	B015	1A		YC065-YR328

WIRE LIST

D280A108

91-21-11

Section W2110

Page 10

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W2112	286A2112				P5 OVHD PANEL TO EE BAY (E2-1/E2-2/E3-1) LA2 (continued)											
6005	20	PA		2-4	34-61-17	D00462		8			GD00516	DC..	1A		YC053-YC055	
6005	20	PA		2-6	34-61-17	D00462		8			GD00516	DC..	1A		YC056-YC058, YC065-YR328	
6005	20	PA		2-5	34-61-17	D00462		8			GD00516	DC..	1A		YC059-YC064	
6006	20	PA		2-3	34-61-17	D00646		38			GD00516	DC..	1A		YC053-YC064	
6006	20	PA		2-4	34-61-17	D00646		38			GD00516	DC..	1A		YC065-YR328	
6007	24	PK		4-0	34-61-17	D00646		39			TB0504X	A013	1A		YC053-YC058	
6007	24	PK		4-3	34-61-17	D00646		39			TB0504X	A013	1A		YC059-YC064	
6007	24	PK		4-7	34-61-17	D00646		39			TB0504X	A013	1A		YC065-YR328	
6008	22	PA		28-9	30-11-11	D00648		5			D40520P	A19			YC053-YC055, YC065-YR328	
6008	22	PA		28-10	30-11-11	D00648		5			D40520P	A19			YC056-YC064	
6009	22	PA		28-9	30-11-11	D00648		6			D40520P	B19			YC053-YC055, YC065-YR328	
6009	22	PA		28-10	30-11-11	D00648		6			D40520P	B19			YC056-YC064	
6010	22	PA		20-5	30-11-11	D00462		21			D48102P	A09			YC053-YC055	
6010	22	PA		20-7	30-11-11	D00462		21			D48102P	A09			YC056-YR328	
6011	20	PA		2-4	30-11-11	D00462		29			GD00516	DC..	1A		YC053-YC055	
6011	20	PA		2-6	30-11-11	D00462		29			GD00516	DC..	1A		YC056-YC058, YC065-YR328	
6011	20	PA		2-5	30-11-11	D00462		29			GD00516	DC..	1A		YC059-YC064	
6012	22	PA		28-9	30-11-11	D00648		3			D40520P	A20			YC053-YC055, YC065-YR328	
6012	22	PA		28-10	30-11-11	D00648		3			D40520P	A20			YC056-YC064	
6013	22	PA		28-9	30-11-11	D00648		4			D40520P	B20			YC053-YC055, YC065-YR328	
6013	22	PA		28-10	30-11-11	D00648		4			D40520P	B20			YC056-YC064	
6014	24	PK		33-9	73-32-11	D02952		8			D40516P	A04			YC053-YC055	
6014	24	PK		34-3	73-32-11	D02952		8			D40516P	A04			YC056-YC058	
6014	24	PK		34-2	73-32-11	D02952		8			D40516P	A04			YC059-YC064	
6014	24	PK		34-1	73-32-11	D02952		8			D40516P	A04			YC065-YR328	
6015	20	PA		1-10	74-31-11	S00266		3B	C		GD00501	DC..	1A		YC053-YC058	
6015	20	PA		1-11	74-31-11	S00266		3B	C		GD00501	DC..	1A		YC059-YR328	
6016	24	PK		37-0	74-31-11	S00266		3A	C		D40516P	B04			YC053-YC055	
6016	24	PK		37-5	74-31-11	S00266		3A	C		D40516P	B04			YC056-YC058	
6016	24	PK		37-6	74-31-11	S00266		3A	C		D40516P	B04			YC059-YR328	
6017	24	PK		37-0	74-31-11	S00266		2A	C		D40516P	A05			YC053-YC055	
6017	24	PK		37-5	74-31-11	S00266		2A	C		D40516P	A05			YC056-YC058	
6017	24	PK		37-6	74-31-11	S00266		2A	C		D40516P	A05			YC059-YR328	

WIRE LIST

D280A108

91-21-11

Section W2110

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To						
Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2112	286A2112			P5 OVHD PANEL TO EE BAY (E2-1/E2-2/E3-1) LA2 (continued)										
6018	20	PA		1-10	74-31-11	S00266	2B	C		GD00501	DC..	1A		YC053-YC058
6018	20	PA		1-11	74-31-11	S00266	2B	C		GD00501	DC..	1A		YC059-YR328
6019	24	B6		36-7	74-31-11	S00858	8	C		D40516P	A07			YC053-YC055
6019	24	B6		37-5	74-31-11	S00858	8	C		D40516P	A07			YC056-YC058
6019	24	B6		37-1	74-31-11	S00858	8	C		D40516P	A07			YC059-YR328
6020	20	CQ		1-6	74-31-11	S00858	7	C		GD00501	DC..	1A		YC053-YC055, YC059-YR328
6020	20	CQ		1-9	74-31-11	S00858	7	C		GD00501	DC..	1A		YC056-YC058
6022	22	PA		34-0	78-36-11	D02952	19			D40596P	B03			YC053-YC055
6022	22	PA		34-6	78-36-11	D02952	19			D40596P	B03			YC056-YC058
6022	22	PA		34-4	78-36-11	D02952	19			D40596P	B03			YC059-YR328
6023	22	PA		20-6	30-11-11	D00648	30			D48102P	A07			YC053-YR328
6024	22	PA		20-5	30-11-11	D00462	24			D48102P	A08			YC053-YC055
6024	22	PA		20-7	30-11-11	D00462	24			D48102P	A08			YC056-YR328
6025	24	PK		33-9	73-21-12	D02952	6			D40516P	B05			YC053-YC055
6025	24	PK		34-3	73-21-12	D02952	6			D40516P	B05			YC056-YC058
6025	24	PK		34-2	73-21-12	D02952	6			D40516P	B05			YC059-YC064
6025	24	PK		34-1	73-21-12	D02952	6			D40516P	B05			YC065-YR328
6026	20	PA		2-0	73-21-12	D02952	18			GD00508	DC..	1A		YC053-YR328
6027	20	PA		2-0	73-21-12	D02952			AC	GD00508	ST..	1A		YC053-YR328
6028	24	PK		34-8	73-23-11	D00462	16			D40516P	A06			YC053-YC055
6028	24	PK		35-4	73-23-11	D00462	16			D40516P	A06			YC056-YR328
6029	20	PA		2-4	73-23-11	D00462	19			GD00516	DC..	1A		YC053-YC055
6029	20	PA		2-6	73-23-11	D00462	19			GD00516	DC..	1A		YC056-YC058, YC065-YR328
6029	20	PA		2-5	73-23-11	D00462	19			GD00516	DC..	1A		YC059-YC064
6030	22	PA		5-1	30-11-11	D00462	11			D40514P	22			YC053-YC055
6030	22	PA		6-1	30-11-11	D00462	11			D40514P	22			YC056-YR328
6031	24	PK		35-6	73-31-11	D00626	21			D40516P	B06			YC053-YC055
6031	24	PK		36-0	73-31-11	D00626	21			D40516P	B06			YC056-YR328
6032	24	PK		8-8	74-31-11	S00266	5A	C		TB0261Y	A007	1A		YC053-YC064
6032	24	PK		8-11	74-31-11	S00266	5A	C		TB0261Y	A007	1A		YC065-YR328
6033	24	PK		8-8	74-31-11	S00266	4A	C		TB0261Y	A007	1A		YC053-YC064
6033	24	PK		8-11	74-31-11	S00266	4A	C		TB0261Y	A007	1A		YC065-YR328
6034	24	PK		8-8	74-31-11	S00266	4B	C		TB0261Y	B007	1A		YC053-YC064
6034	24	PK		8-11	74-31-11	S00266	4B	C		TB0261Y	B007	1A		YC065-YR328
6035	24	PK		8-8	74-31-11	S00266	5B	C		TB0261Y	B007	1A		YC053-YC064
6035	24	PK		8-11	74-31-11	S00266	5B	C		TB0261Y	B007	1A		YC065-YR328
6039	20	CQ		29-3	28-43-11	D40598P	B07			D00626	10			YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W2110

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2112	286A2112			P5 OVHD PANEL TO EE BAY (E2-1/E2-2/E3-1) LA2 (continued)											
6040	20		PA		29-3	28-23-11	D40598P	A06			D00626	39			YC053-YC055, YC059-YD157
6040	20		PA		29-4	28-23-11	D40598P	A06			D00626	39			YC056-YC058
6040	20		CQ		29-3	28-23-11	D40598P	A06			D00626	39			YD158-YR328
6041	20		PA		29-3	28-23-11	D40598P	A07			D00626	35			YC053-YC055, YC059-YD157
6041	20		PA		29-4	28-23-11	D40598P	A07			D00626	35			YC056-YC058
6041	20		CQ		29-3	28-23-11	D40598P	A07			D00626	35			YD158-YR328
6042	20		PA		29-3	28-23-11	D40598P	A08			D00626	37			YC053-YC055, YC059-YD157
6042	20		PA		29-4	28-23-11	D40598P	A08			D00626	37			YC056-YC058
6042	20		CQ		29-3	28-23-11	D40598P	A08			D00626	37			YD158-YR328
6043	20		PA		7-0	28-23-11	GD00261	AC..	1A		D00626	36			YC053-YD157
6043	20		CQ		7-0	28-23-11	GD00261	AC..	1A		D00626	36			YD158-YR328
6044	20		PA		7-0	28-23-11	GD00261	AC..	1A		D00626	34			YC053-YD157
6044	20		CQ		7-0	28-23-11	GD00261	AC..	1A		D00626	34			YD158-YR328
6045	20		PA		7-0	28-23-11	GD00261	AC..	1A		D00626	38			YC053-YD157
6045	20		CQ		7-0	28-23-11	GD00261	AC..	1A		D00626	38			YD158-YR328
6046	20		CQ		29-3	28-43-11	D40598P	B05			D00626	28			YC053-YC055, YC059-YR328
6046	20		CQ		29-4	28-43-11	D40598P	B05			D00626	28			YC056-YC058
6047	20		CQ		29-3	28-43-11	D40598P	A04			D00626	26			YC053-YC055, YC059-YR328
6047	20		CQ		29-4	28-43-11	D40598P	A04			D00626	26			YC056-YC058
6048	20		CQ		29-6	28-43-11	D40520P	A01			D00626	2			YC053-YC055, YC059-YR328
6048	20		CQ		29-7	28-43-11	D40520P	A01			D00626	2			YC056-YC058
6049	22		CQ		5-1	30-21-11	D00462	31			D40514P	23			YC053-YC055
6049	22		CQ		6-1	30-21-11	D00462	31			D40514P	23			YC056-YR328
6050	20		CQ		7-10	80-11-11	S00266	1A	C		D40514P	8			YC053-YC055
6050	20		CQ		8-2	80-11-11	S00266	1A	C		D40514P	8			YC056-YC058
6050	20		CQ		8-3	80-11-11	S00266	1A	C		D40514P	8			YC059-YR328
6053	20		CQ		3-3	28-43-11	GD00510	DC..	1		D00626	6			YD158-YR328
6054	20		CQ		29-3	28-23-11	D40598P	A01			D00626	18			YD160-YR328
6056	20		CQ		7-0	28-23-11	GD00261	AC..	1A		D00626	9			YD160-YR328
8001	22		PA		4-0	31-31-11	D00483	10			D40514P	21			YC053-YC055
8001	22		PA		4-4	31-31-11	D00483	10			D40514P	21			YC056-YR328
8002	22		PA		4-0	31-31-11	D00483	7			D40514P	17			YC053-YC055
8002	22		PA		4-4	31-31-11	D00483	7			D40514P	17			YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W2110

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type
W2112	286A2112			P5 OVHD PANEL TO EE BAY (E2-1/E2-2/E3-1) LA2 (continued)										
8003	22	PA		19-4	31-31-11	D00483		18		D48102P	B01			YC053-YC055, YC059-YR328
8003	22	PA		19-5	31-31-11	D00483		18		D48102P	B01			YC056-YC058
8004	22	PA		19-4	31-31-11	D00483		2		D48102P	B02			YC053-YC055, YC059-YR328
8004	22	PA		19-5	31-31-11	D00483		2		D48102P	B02			YC056-YC058
8005	22	PA		33-10	31-31-11	D00483		11		D40596P	A05			YC053-YC055
8005	22	PA		34-4	31-31-11	D00483		11		D40596P	A05			YC056-YR328
8006	22	PA		33-10	31-31-11	D00483		20		D40596P	A10			YC053-YC055
8006	22	PA		34-4	31-31-11	D00483		20		D40596P	A10			YC056-YR328
8007	22	CQ		33-9	27-32-11	D02349		5		D40596P	A03			YC053-YC055
8007	22	CQ		34-3	27-32-11	D02349		5		D40596P	A03			YC056-YC058
8007	22	CQ		34-2	27-32-11	D02349		5		D40596P	A03			YC059-YC064
8007	22	CQ		34-1	27-32-11	D02349		5		D40596P	A03			YC065-YR328
8008	20	CQ		1-7	27-32-11	D02349		4		GD00508	DC..	1A		YC053-YR328
8009	22	CQ		35-0	34-51-41	D00553		18		D40516P	B10			YC053-YC055
8009	22	CQ		35-6	34-51-41	D00553		18		D40516P	B10			YC056-YC058
8009	22	CQ		35-7	34-51-41	D00553		18		D40516P	B10			YC059-YR328
8010	20	CQ		2-8	34-51-41	D00553		19		GD00517	DC..	1A		YC053-YC058
8010	20	CQ		2-9	34-51-41	D00553		19		GD00517	DC..	1A		YC059-YR328
8011	20	PA		34-11	22-23-11	D00630		4		D40596P	A07			YC053-YC055
8011	20	PA		35-6	22-23-11	D00630		4		D40596P	A07			YC056-YC058
8011	20	PA		35-5	22-23-11	D00630		4		D40596P	A07			YC059-YR328
8012	22	PA		34-11	22-23-11	D00630		19		D40596P	B07			YC053-YC055
8012	22	PA		35-6	22-23-11	D00630		19		D40596P	B07			YC056-YC058
8012	22	PA		35-5	22-23-11	D00630		19		D40596P	B07			YC059-YR328
8013	20	PA		34-11	22-23-11	D00630		26		D40596P	A08			YC053-YC055
8013	20	PA		35-6	22-23-11	D00630		26		D40596P	A08			YC056-YC058
8013	20	PA		35-5	22-23-11	D00630		26		D40596P	A08			YC059-YR328
8014	20	PA		4-5	22-23-11	D00630		12		TB0505Y	A007	1A		YC053-YC058
8014	20	PA		4-7	22-23-11	D00630		12		TB0505Y	A007	1A		YC059-YC064
8014	20	PA		4-9	22-23-11	D00630		12		TB0505Y	A007	1A		YC065-YR328
8015	20	PA		4-5	22-23-11	D00630		27		TB0505Y	A007	1A		YC053-YC058
8015	20	PA		4-7	22-23-11	D00630		27		TB0505Y	A007	1A		YC059-YC064
8015	20	PA		4-9	22-23-11	D00630		27		TB0505Y	A007	1A		YC065-YR328
8016	20	PA		32-10	22-23-11	TB0505Y		A007	1A	D40596P	B08			YC053-YC055
8016	20	PA		33-4	22-23-11	TB0505Y		A007	1A	D40596P	B08			YC056-YC058, YC065-YR328
8016	20	PA		33-3	22-23-11	TB0505Y		A007	1A	D40596P	B08			YC059-YC064

WIRE LIST

D280A108

91-21-11

Section W2110

Page 14

Nov 12/2012

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2112	286A2112			P5 OVHD PANEL TO EE BAY (E2-1/E2-2/E3-1) LA2 (continued)											
8017	20		PA		2-5	22-23-11	D00630			17	GD00517	DC..	1A		YC053-YR328
8018	20		PA		2-5	22-23-11	D00630			14	GD00517	DC..	1A		YC053-YR328
8019	22		PA		34-11	22-23-11	D00624			23	D40596P	A09			YC053-YC055
8019	22		PA		35-5	22-23-11	D00624			23	D40596P	A09			YC056-YC058
8019	22		PA		35-4	22-23-11	D00624			23	D40596P	A09			YC059-YR328
8020	20		PA		34-11	22-23-11	D00624			47	D40596P	B09			YC053-YC055
8020	20		PA		35-5	22-23-11	D00624			47	D40596P	B09			YC056-YC058
8020	20		PA		35-4	22-23-11	D00624			47	D40596P	B09			YC059-YR328
8021	24		PK		34-11	31-31-15	D00624			32	D40596P	A04			YC053-YC055
8021	24		PK		35-5	31-31-15	D00624			32	D40596P	A04			YC056-YC058
8021	24		PK		35-4	31-31-15	D00624			32	D40596P	A04			YC059-YR328
8022	22		PA		34-10	34-21-15	D01817			35	D40516P	B02			YC053-YC055
8022	22		PA		35-4	34-21-15	D01817			35	D40516P	B02			YC056-YC058
8022	22		PA		35-5	34-21-15	D01817			35	D40516P	B02			YC059-YR328
8023	22		PA		35-0	34-21-15	D00553			42	D40516P	A02			YC053-YC055
8023	22		PA		35-6	34-21-15	D00553			42	D40516P	A02			YC056-YC058
8023	22		PA		35-7	34-21-15	D00553			42	D40516P	A02			YC059-YR328
8024	20		PA		2-8	34-21-15	D00553			41	GD00517	AC..	1A		YC053-YC058
8024	20		PA		2-9	34-21-15	D00553			41	GD00517	AC..	1A		YC059-YR328
8026	20		CQ		2-11	34-61-18	D40512P			5	D40514P		2		YC053-YC055
8026	20		CQ		3-4	34-61-18	D40512P			5	D40514P		2		YC056-YC058
8026	20		CQ		3-4	31-32-15	D40512P			5	D40514P		2		YC059-YR328
8027	20		PA		5-5	34-21-15	D40514P			1	D00553		54		YC053-YC055
8027	20		PA		6-3	34-21-15	D40514P			1	D00553		54		YC056-YC064
8027	20		PA		6-4	34-21-15	D40514P			1	D00553		54		YC065-YR328
FRAA					0-0	21-31-22	D10724				AA	GD00516	ST..	1A	YC053-YR328
W2114	286A2114			P5 OVHD TO AB0340A/AB0340B AND AE0101A DISC BRACKET (LB2)											
0001	18		PA		8-4	33-41-11	S00098			1	C	D40522P		10	ALL
0002	18		PA		7-8	33-41-11	S00098			2	C	TB0502V	A025	1	YC051-YC052
0002	18		PA		7-5	33-41-11	S00098			2	C	TB0502V	A025	1	YC053-YC058
0002	18		PA		7-7	33-41-11	S00098			2	C	TB0502V	A025	1	YC059-YC064
0002	18		PA		7-10	33-41-11	S00098			2	C	TB0502V	A025	1	YC065-YR328
0003	18		PA		10-7	33-41-11	TB0502V			A025	1	D40196P		4	18
															YC051-YC052,
															YC059-YC064
0003	18		PA		10-8	33-41-11	TB0502V			A025	1	D40196P		4	18
															YC053-YC058,
															YC065-YR328
0006	20		PA		6-1	33-51-11	S00007			3C	B	TB0506Y	B007	1A	YC051-YC052
0006	20		PA		6-0	33-51-11	S00007			3C	B	TB0506Y	B007	1A	YC053-YC058

WIRE LIST

D280A108

91-21-11

Section W2110

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2114	286A2114				P5 OVHD TO AB0340A/AB0340B AND AE0101A DISC BRACKET (LB2) (continued)											
0006	20	PA			6-2	33-51-11		S00007	3C	B		TB0506Y	B007	1A		YC059-YC064
0006	20	PA			6-5	33-51-11		S00007	3C	B		TB0506Y	B007	1A		YC065-YR328
0007	20	PA			5-4	33-51-11		S00007	3NO	B	*	TB0505Y	A001	1A		YC051-YC052
0007	20	PA			5-5	33-51-11		S00007	3NO	B	*	TB0505Y	A001	1A		YC053-YC058
0007	20	PA			6-2	33-51-11		S00007	3NO	B	*	TB0505Y	A001	1A		YC059-YC064
0007	20	PA			6-3	33-51-11		S00007	3NO	B	*	TB0505Y	A001	1A		YC065-YR328
0008	20	PA			0-7	33-51-11		S00007	3NO	B	*	S00007	4NO	B		ALL
0009	20	PA			6-1	33-51-11		S00007	4C	B		TB0506Y	B007	1A		YC051-YC052
0009	20	PA			6-0	33-51-11		S00007	4C	B		TB0506Y	B007	1A		YC053-YC058
0009	20	PA			6-2	33-51-11		S00007	4C	B		TB0506Y	B007	1A		YC059-YC064
0009	20	PA			6-5	33-51-11		S00007	4C	B		TB0506Y	B007	1A		YC065-YR328
0010	20	PA			6-1	33-51-11		L00001	1	B		TB0506Y	B007	1A		YC051-YC052, YC059-YC064
0010	20	PA			5-5	33-51-11		L00001	1	B		TB0506Y	B007	1A		YC053-YC058
0010	20	PA			6-4	33-51-11		L00001	1	B		TB0506Y	B007	1A		YC065-YR328
0011	20	PA			3-9	33-51-11		D00483	8			TB0506Y	B007	1A		YC051-YC052
0011	20	PA			3-4	33-51-11		D00483	8			TB0506Y	B007	1A		YC053-YC058
0011	20	PA			3-7	33-51-11		D00483	8			TB0506Y	B007	1A		YC059-YC064
0011	20	PA			3-5	33-51-11		D00483	8			TB0506Y	B007	1A		YC065-YR328
0012	20	PA			3-2	33-51-11		TB0505Y	A001	1A		D40522P	1			YC051-YC058
0012	20	PA			3-1	33-51-11		TB0505Y	A001	1A		D40522P	1			YC059-YC064
0012	20	PA			3-0	33-51-11		TB0505Y	A001	1A		D40522P	1			YC065-YR328
0013	20	PA			10-5	33-51-11		TB0505Y	A001	1A		D40296P	1			YC051-YC052
0013	20	PA			10-8	33-51-11		TB0505Y	A001	1A		D40296P	1			YC053-YC058
0013	20	PA			10-7	33-51-11		TB0505Y	A001	1A		D40296P	1			YC059-YR328
0014	22	PA			10-5	33-51-11		TB0505Y	B001	1A		D40296P	2			YC051-YC052
0014	22	PA			10-8	33-51-11		TB0505Y	B001	1A		D40296P	2			YC053-YC058
0014	22	PA			10-7	33-51-11		TB0505Y	B001	1A		D40296P	2			YC059-YR328
0015	22	PA			10-5	33-51-11		TB0505Y	B003	1A		D40296P	3			YC051-YC052
0015	22	PA			10-8	33-51-11		TB0505Y	B003	1A		D40296P	3			YC053-YC058
0015	22	PA			10-7	33-51-11		TB0505Y	B003	1A		D40296P	3			YC059-YR328
0016	22	PA			10-5	33-51-11		TB0505Y	B001	1A		D40196P	2			YC051-YC052
0016	22	PA			10-9	33-51-11		TB0505Y	B001	1A		D40196P	2			YC053-YC058
0016	22	PA			10-8	33-51-11		TB0505Y	B001	1A		D40196P	2			YC059-YC064
0016	22	PA			10-7	33-51-11		TB0505Y	B001	1A		D40196P	2			YC065-YR328
0017	22	PA			10-5	33-51-11		TB0505Y	B003	1A		D40196P	1			YC051-YC052
0017	22	PA			10-9	33-51-11		TB0505Y	B003	1A		D40196P	1			YC053-YC058
0017	22	PA			10-8	33-51-11		TB0505Y	B003	1A		D40196P	1			YC059-YC064
0017	22	PA			10-7	33-51-11		TB0505Y	B003	1A		D40196P	1			YC065-YR328

WIRE LIST

D280A108

91-21-11

Section W2110

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W2114	286A2114				P5 OVHD TO AB0340A/AB0340B AND AE0101A DISC BRACKET (LB2) (continued)										
0018	18		PA		10-7	33-41-11	TB0502V	A025	1		D40296P	21			YC051-YC052
0018	18		PA		10-8	33-41-11	TB0502V	A025	1		D40296P	21			YC053-YC058, YC065-YR328
0018	18		PA		10-6	33-41-11	TB0502V	A025	1		D40296P	21			YC059-YC064
0019	20		PA		7-7	33-44-11	TB0501X			AA	GD00501	ST..	1A		ALL
0020	20		PA		8-7	33-51-11	D40522P		5		D40196P	5			YC051-YC052
0020	20		PA		10-0	33-51-11	D40522P		5		D40196P	5			YC053-YR328
0021	20		PA		8-7	33-51-11	D40522P		6		D40296P	5			YC051-YC052
0021	20		PA		10-0	33-51-11	D40522P		6		D40296P	5			YC053-YR328
0022	20		PA		12-8	33-51-12	D02970	= 1			D40296P	38			YC051-YC052
0022	20		PA		12-7	33-51-12	D02970	= 1			D40296P	38			YC053-YR328
0023	20		PA		7-3	33-42-11	S00258		2	C	D40522P	9			YC051-YC052, YC059-YC064
0023	20		PA		7-4	33-42-11	S00258		2	C	D40522P	9			YC053-YC058, YC065-YL999, YR301-YR328
0023	20		PA		7-6	33-42-11	S00258		2	C	D40522P	9			YN231-YN501
0024	18		PA		21-7	33-42-11	S00258		1	C	TB1806V	A015	1		YC051-YC052
0024	18		PA		21-8	33-42-11	S00258		1	C	TB1806V	A015	1		YC053-YC064, YN231-YN501
0024	18		PA		21-11	33-42-11	S00258		1	C	TB1806V	A015	1		YC065-YL999, YR301-YR328
0025	20		PA		7-7	33-51-12	D02992	= 1			SP00302		S		YC051-YC052
0025	20		PA		6-11	33-51-12	D02992	= 1			TB0261Y	A005	1A		YC053-YR328
0027	20		PA		22-7	21-42-11	D40196P		9		D48104P	A08			YC051-YC052
0027	20		PA		22-6	21-42-11	D40196P		9		D48104P	A08			YC053-YR328
0028	20		PA		22-7	21-42-11	D40296P		9		D48104P	A09			YC051-YC052
0028	20		PA		22-5	21-42-11	D40296P		9		D48104P	A09			YC053-YR328
0030	20		PA		22-7	52-71-13	D40196P		17		D48104P	B01			YC051-YC052
0030	20		PA		22-6	52-71-13	D40196P		17		D48104P	B01			YC053-YR328
0031	20		PA		22-7	52-71-13	D40196P		18		D48104P	B02			YC051-YC052
0031	20		PA		22-6	52-71-13	D40196P		18		D48104P	B02			YC053-YR328
0035	20		PA		22-7	52-71-14	D40296P		23		D48104P	B04			YC051-YC052
0035	20		PA		22-5	52-71-14	D40296P		23		D48104P	B04			YC053-YR328
0036	20		CQ		22-7	52-71-14	D40296P		24		D48104P	B05			YC051-YC052
0036	20		CQ		22-5	52-71-14	D40296P		24		D48104P	B05			YC053-YR328
0040	20		PA		22-7	52-71-13	D40196P		22		D48104P	B03			YC051-YC052
0040	20		PA		22-6	52-71-13	D40196P		22		D48104P	B03			YC053-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W2110

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W2114	286A2114	P5 OVHD TO AB0340A/AB0340B AND AE0101A DISC BRACKET (LB2) (continued)													
0045	20	CQ		22-7 52-71-14	D40296P	27			D48104P	B06				YC051-YC052	
0045	20	CQ		22-5 52-71-14	D40296P	27			D48104P	B06				YC053-YL999, YR301-YR328	
1201	20	X1	DA	10-9 33-44-11	TB0501X	B026	1A		D40296P	30				YC051-YC052	
1201	20	X1	DA	11-0 33-44-11	TB0501X	B026	1A		D40296P	30				YC053-YC058	
1201	20	X1	DA	10-11 33-44-11	TB0501X	B026	1A		D40296P	30				YC059-YC064	
1201	20	X1	DA	11-1 33-44-11	TB0501X	B026	1A		D40296P	30				YC065-YR328	
1201Z			DA	0-0 33-44-11	TB0501X			AA	D40296P	S/R				ALL	
5501	22	CQ		21-2 21-27-31	S00870	5	C		D48104P	A01				YC051-YC052	
5501	22	CQ		21-4 21-27-31	S00870	5	C		D48104P	A01				YC053-YC058	
5501	22	CQ		21-3 21-27-31	S00870	5	C		D48104P	A01				YC059-YC064	
5501	22	CQ		21-5 21-27-31	S00870	5	C		D48104P	A01				YC065-YR328	
5502	22	CQ		4-0 21-27-31	S00870	4	C		GD00505	DC..	1A			YC051-YC052	
5502	22	CQ		3-11 21-27-31	S00870	4	C		GD00515	DC..	1A			YC053-YC058	
5502	22	CQ		3-10 21-27-31	S00870	4	C		GD00515	DC..	1A			YC059-YC064	
5502	22	CQ		4-0 21-27-31	S00870	4	C		GD00515	DC..	1A			YC065-YR328	
5504	20	PA		2-5 21-61-51	D00090	4			GD00506	DC..	1A			YC051-YC052	
5504	20	PA		2-6 21-61-51	D00090	4			GD00506	DC..	1A			YC053-YC058	
5504	20	PA		2-2 21-61-51	D00090	4			GD00506	DC..	1A			YC059-YL999, YR301-YR328	
5505	20	PA		2-5 21-61-51	D00090	5			GD00506	DC..	1A			YC051-YC052	
5505	20	PA		2-6 21-61-51	D00090	5			GD00506	DC..	1A			YC053-YC058	
5505	20	PA		2-2 21-61-51	D00090	5			GD00506	DC..	1A			YC059-YR328	
5506	20	PA		12-7 21-61-51	D00090	4			D40296P	36				YN231-YN501	
5507	24	PK		1-4 21-61-51	D00090	3			D03998	20				YC051-YC052	
5507	24	PK		1-7 21-61-51	D00090	3			D03998	20				YC053-YC058	
5507	24	PK		1-5 21-61-51	D00090	3			D03998	20				YC059-YL999, YR301-YR328	
5507	20	PA		1-8 21-61-51	D00090	3			D00656	6				YN231-YN501	
5508	20	PA		12-10 21-61-51	D00656	9			D40296P	18				YN231-YN501	
5509	20	PA		12-10 21-61-51	D00656	10			D40296P	17				YN231-YN501	
5510	24	PK		10-7 21-61-22	TB0504Y	B011	1A		D40296P	28				YN231-YN501	
5511	24	PK		10-6 21-61-22	TB0504X	A015	1A		D40296P	25				YN231-YN501	
5512	24	PK		10-6 21-61-22	TB0504X	A016	1A		D40296P	26				YN231-YN501	
5513	22	CQ		5-0 30-31-11	D00644	42			D40522P	3				YC051-YC052, YC059-YR328	
5513	22	CQ		4-10 30-31-11	D00644	42			D40522P	3				YC053-YC058	
5514	22	PA		5-0 30-31-11	D00644	39			D40522P	12				YC051-YC052, YC059-YR328	

WIRE LIST

D280A108

91-21-11

Section W2110

Page 18

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W2114	286A2114				P5 OVHD TO AB0340A/AB0340B AND AE0101A DISC BRACKET (LB2) (continued)											
5514	22	PA		4-10	30-31-11	D00644		39			D40522P	12			YC053-YC058	
5515	22	PA		5-0	30-31-11	D00644		46			D40522P	11			YC051-YC052, YC059-YR328	
5515	22	PA		4-10	30-31-11	D00644		46			D40522P	11			YC053-YC058	
5516	20	PA		2-3	30-31-11	D00644		55			GD00506	DC..	1A		YC051-YC052	
5516	20	PA		2-2	30-31-11	D00644		55			GD00506	DC..	1A		YC053-YR328	
5517	22	CQ		19-6	30-31-11	D00644		41			D48104P	A02			YC051-YC052	
5517	22	CQ		19-4	30-31-11	D00644		41			D48104P	A02			YC053-YC058	
5517	22	CQ		19-7	30-31-11	D00644		41			D48104P	A02			YC059-YR328	
5518	22	PA		19-6	30-31-11	D00644		38			D48104P	A03			YC051-YC052	
5518	22	PA		19-4	30-31-11	D00644		38			D48104P	A03			YC053-YC058	
5518	22	PA		19-7	30-31-11	D00644		38			D48104P	A03			YC059-YR328	
5519	22	PA		19-6	30-31-11	D00644		44			D48104P	A04			YC051-YC052	
5519	22	PA		19-4	30-31-11	D00644		44			D48104P	A04			YC053-YC058	
5519	22	PA		19-7	30-31-11	D00644		44			D48104P	A04			YC059-YR328	
5520	22	PA		19-6	30-31-11	D00644		45			D48104P	A05			YC051-YC052	
5520	22	PA		19-4	30-31-11	D00644		45			D48104P	A05			YC053-YC058	
5520	22	PA		19-7	30-31-11	D00644		45			D48104P	A05			YC059-YR328	
5521	24	PK		12-5	21-61-51	D41838P		1			D03998	18			YC051-YC052	
5521	24	PK		12-7	21-61-51	D41838P		1			D03998	18			YC053-YL999, YR301-YR328	
5522	24	PK		12-5	21-61-51	D41838P		2			D03998	17			YC051-YC052	
5522	24	PK		12-7	21-61-51	D41838P		2			D03998	17			YC053-YL999, YR301-YR328	
5523	24	PK		12-5	21-61-51	D41838P		3			D03998	3			YC051-YC052	
5523	24	PK		12-7	21-61-51	D41838P		3			D03998	3			YC053-YL999, YR301-YR328	
5524	22	PA		5-0	30-31-11	D00644		43			D40522P	8			YC051-YC052, YC059-YR328	
5524	22	PA		4-10	30-31-11	D00644		43			D40522P	8			YC053-YC058	
5525	24	PK		12-6	21-61-51	D41838P		4			D03996	13			YC051-YC052	
5525	24	PK		12-8	21-61-51	D41838P		4			D03996	13			YC053-YC058	
5525	20	GK		12-8	21-61-51	D41838P		4			D03996	13			YC059-YL999, YR301-YR328	
8001	22	PA		20-2	34-41-11	D00553		51			D48104P	A06			YC051-YC052	
8001	22	PA		20-6	34-41-11	D00553		51			TB1808X	B002	1A		YC053-YC058	
8001	22	PA		20-5	34-41-11	D00553		51			TB1808X	B002	1A		YC059-YC064	
8001	22	PA		20-7	34-41-11	D00553		51			TB1808X	B002	1A		YC065-YR328	
8002	20	PA		3-0	34-41-11	D00553		50			GD00505	DC..	1A		YC051-YC052	

WIRE LIST

D280A108

91-21-11

Section W2110

Page 19

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2114		286A2114			P5 OVHD TO AB0340A/AB0340B AND AE0101A DISC BRACKET (LB2) (continued)											
8002		20		PA		2-10	34-41-11	D00553		50		GD00515	DC..	1A		YC053-YC058
8002		20		PA		2-9	34-41-11	D00553		50		GD00515	DC..	1A		YC059-YR328
A-AG						0-0	33-51-12	R00340		=G		GD00261	DC..	1A		YC051-YC052
A-AG						0-0	33-51-12	R00340		=G		GB00261	DC..	1A		YC053-YR328
A-AP						0-0	33-51-12	R00340		=P		SP00302		S		YC051-YC052
A-AP						0-0	33-51-12	R00340		=P		TB0261Y	A005	1A		YC053-YR328

WIRE LIST

D280A108

91-21-11

Section W2110

Page 20 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I	W2132	286A2132	P91 TO P6 (115V AC XFR BUS 1 SEC 2)												
I	0001	08	CQ		25-8	24-51-11	D11414	A			TB5060H	1	E		YC051-YD158
I	0001	08	CQ		26-2	24-51-14	D11414	A			TB5060H	1	E		YL951-YR328
I	0002	08	CQ		25-7	24-51-11	D11414	B			TB5060H	2	E		YC051-YD158
I	0002	08	CQ		26-1	24-51-14	D11414	B			TB5060H	2	E		YL951-YR328
I	0003	08	CQ		25-7	24-51-11	D11414	C			TB5060H	3	E		YC051-YD158
I	0003	08	CQ		26-1	24-51-14	D11414	C			TB5060H	3	E		YL951-YR328
I	0004	08	CQ		4-1	24-51-11	D11414	E			GD00912	AC..	F		YC051-YC055
I	0004	08	CQ		3-10	24-51-11	D11414	E			GD00912	AC..	F		YC056-YD158
I	0004	08	CQ		3-8	24-51-11	D11414	E			GD00912	AC..	F		YL951-YR328
I	0005	08	CQ		27-6	24-51-15	D11414	F			TB5060L	1	E		YL951-YR328
I	0006	08	CQ		27-5	24-51-15	D11414	G			TB5060L	2	E		YL951-YR328
I	0007	08	CQ		27-4	24-51-15	D11414	D			TB5060L	3	E		YL951-YR328
I	W2134	286A2134	P91 TO P18 (115V AC XFR BUS 1 SEC 2 AND 115V AC MAIN BUS)												
I	0501	10	CQ		19-6	24-51-11	D11412	A			TB5180E	1	E		YC051-YC055
I	0501	10	CQ		19-5	24-51-11	D11412	A			TB5180E	1	E		YC056-YD158
I	0501	10	CQ		20-2	24-51-13	D11412	A			TB5180E	1	E		YD160-YR328
I	0502	10	CQ		19-4	24-51-11	D11412	B			TB5180E	3	E		YC051-YD158
I	0502	10	CQ		20-1	24-51-13	D11412	B			TB5180E	3	E		YD160-YR328
I	0503	10	CQ		19-3	24-51-11	D11412	C			TB5180E	5	E		YC051-YC055
I	0503	10	CQ		19-2	24-51-11	D11412	C			TB5180E	5	E		YC056-YD158
I	0503	10	CQ		19-11	24-51-13	D11412	C			TB5180E	5	E		YD160-YR328
I	0504	10	CQ		19-2	24-51-11	D11412	G			TB5180E	7	E		YC051-YC055
I	0504	10	CQ		19-1	24-51-11	D11412	G			TB5180E	7	E		YC056-YD158
I	0504	10	CQ		19-10	24-51-12	D11412	G			TB5180E	7	E		YD160-YR328
I	0505	10	CQ		19-1	24-51-11	D11412	E			TB5180E	8	E		YC051-YC055
I	0505	10	CQ		19-0	24-51-11	D11412	E			TB5180E	8	E		YC056-YD158
I	0505	10	CQ		19-9	24-51-12	D11412	E			TB5180E	8	E		YD160-YR328
I	0506	10	CQ		19-1	24-51-11	D11412	D			TB5180E	9	E		YC051-YC055
I	0506	10	CQ		19-0	24-51-11	D11412	D			TB5180E	9	E		YC056-YD158
I	0506	10	CQ		19-9	24-51-12	D11412	D			TB5180E	9	E		YD160-YR328
I	W2135	286A2135	P5, E5-2												
I	0001	22	PA		22-10	34-21-21	D02183	9			D45237J	A01			YC051-YC052
I	0001	22	PA		22-8	34-21-21	D02183	9			D45237J	A01			YC053-YC058
I	0001	22	PA		22-9	34-21-21	D02183	9			D45237J	A01			YC059-YR328
I	0002	20	PA		1-11	34-21-21	D02183	8			GD00509	ST..	1A		YC051-YC052
I	0002	20	PA		2-1	34-21-21	D02183	8			GD00509	ST..	1A		YC053-YC057
I	0002	20	PA		4-0	34-21-21	D02183	8			GD00509	ST..	1A		YC058

WIRE LIST

D280A108

91-21-11

Section W2130

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2135	286A2135			P5, E5-2 (continued)											
0002	20		PA		4-3	34-21-21	D02183		8		GD00509	ST..	1A		YC059-YR328
0003	22		PA		22-11	34-21-21	D02173		11		D45237J	A06			YC051-YC052
0003	22		PA		22-9	34-21-21	D02173		11		D45237J	A06			YC053-YC058
0003	22		PA		22-8	34-21-21	D02173		11		D45237J	A06			YC059-YR328
0004	22		PA		22-11	34-21-21	D02173		12		D45237J	A07			YC051-YC052
0004	22		PA		22-9	34-21-21	D02173		12		D45237J	A07			YC053-YC058
0004	22		PA		22-8	34-21-21	D02173		12		D45237J	A07			YC059-YR328
0005	22		PA		22-11	34-21-21	D02173		13		D45237J	A08			YC051-YC052
0005	22		PA		22-9	34-21-21	D02173		13		D45237J	A08			YC053-YC058
0005	22		PA		22-8	34-21-21	D02173		13		D45237J	A08			YC059-YR328
0006	22		PA		22-11	34-21-21	D02173		14		D45237J	A09			YC051-YC052
0006	22		PA		22-9	34-21-21	D02173		14		D45237J	A09			YC053-YC058
0006	22		PA		22-8	34-21-21	D02173		14		D45237J	A09			YC059-YR328
0007	22		PA		22-11	34-21-21	D02173		15		D45237J	A10			YC051-YC052
0007	22		PA		22-9	34-21-21	D02173		15		D45237J	A10			YC053-YC058
0007	22		PA		22-8	34-21-21	D02173		15		D45237J	A10			YC059-YR328
0008	22		PA		22-11	34-21-21	D02173		17		D45237J	A11			YC051-YC052
0008	22		PA		22-9	34-21-21	D02173		17		D45237J	A11			YC053-YC058
0008	22		PA		22-8	34-21-21	D02173		17		D45237J	A11			YC059-YR328
0009	22		PA		17-3	34-21-21	D02173		16		D40623P	2			YC051-YC052
0009	22		PA		17-1	34-21-21	D02173		16		D40623P	2			YC053-YC058
0009	22		PA		17-0	34-21-21	D02173		16		D40623P	2			YC059-YC064
0009	22		PA		17-2	34-21-21	D02173		16		D40623P	2			YC065-YR328
0010	22		PA		17-3	34-58-11	D02173		19		D40623P	1			YC051-YC052
0010	22		PA		17-1	34-58-11	D02173		19		D40623P	1			YC053-YC058
0010	22		PA		17-0	34-58-11	D02173		19		D40623P	1			YC059-YC064
0010	22		PA		17-2	34-58-11	D02173		19		D40623P	1			YC065-YR328
0013	22		PA		12-5	34-21-21	D40623P		3		D45237J	A16			YC051-YC064
0013	22		PA		12-6	34-21-21	D40623P		3		D45237J	A16			YC065-YR328
0014	22		PA		12-5	34-21-21	D40623P		4		D45237J	A17			YC051-YC064
0014	22		PA		12-6	34-21-21	D40623P		4		D45237J	A17			YC065-YR328
0015	22		PA		12-5	34-21-21	D40623P		5		D45237J	A18			YC051-YC064
0015	22		PA		12-6	34-21-21	D40623P		5		D45237J	A18			YC065-YR328
0016	24		PK		24-1	31-62-25	D01817		45		D45237J	B01			YC051-YC052
0016	24		PK		23-10	31-62-25	D01817		45		D45237J	B01			YC053-YC058
0016	24		PK		23-11	31-62-25	D01817		45		D45237J	B01			YC059-YR328
0017	24		PK		24-1	31-62-25	D01817		46		D45237J	B02			YC051-YC052
0017	24		PK		23-10	31-62-25	D01817		46		D45237J	B02			YC053-YC058
0017	24		PK		23-11	31-62-25	D01817		46		D45237J	B02			YC059-YR328

WIRE LIST

D280A108

91-21-11

Section W2130

Page 2

Nov 12/2012

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W2135	286A2135			P5, E5-2 (continued)										
0018	24		PK		24-1	31-62-25	D01817		47		D45237J	B03		YC051-YC052
0018	24		PK		23-10	31-62-25	D01817		47		D45237J	B03		YC053-YC058
0018	24		PK		23-11	31-62-25	D01817		47		D45237J	B03		YC059-YR328
0019	22		PA		2-9	31-62-25	D01817		48		GD00505	DC..	1A	YC051-YC052
0019	22		PA		2-7	31-62-25	D01817		48		GD00515	DC..	1A	YC053-YR328
0021	24		PK		12-5	31-62-25	D40623P		8		D45237J	B05		YC051-YC064
0021	24		PK		12-6	31-62-25	D40623P		8		D45237J	B05		YC065-YR328
0022	22		CQ		23-3	34-21-22	D00638		13		D45237J	B13		YC051-YC052, YC059-YR328
0022	22		CQ		23-1	34-21-22	D00638		13		D45237J	B13		YC053-YC058
0023	22		CQ		23-3	34-21-22	D00638		15		D45237J	B14		YC051-YC052, YC059-YR328
0023	22		CQ		23-1	34-21-22	D00638		15		D45237J	B14		YC053-YC058
0024	22		PA		24-1	34-51-41	D45237J		B06		D01817	16		YC051-YC052
0024	22		PA		23-10	34-51-41	D45237J		B06		D01817	16		YC053-YC058
0024	22		PA		23-11	34-51-41	D45237J		B06		D01817	16		YC059-YR328
0025	20		PA		2-9	34-51-41	D01817		14		GD00505	DC..	1A	YC051-YC052
0025	20		PA		2-7	34-51-41	D01817		14		GD00515	DC..	1A	YC053-YR328
0026	20		PA		2-9	34-51-41	D01817		15		GD00505	DC..	1A	YC051-YC052
0026	20		PA		2-7	34-51-41	D01817		15		GD00515	DC..	1A	YC053-YR328
0027	22		PA		21-0	34-51-41	TB0608X	B001	1A		D01817	13		YC051-YC052
0027	22		PA		20-9	34-51-41	TB0608X	B001	1A		D01817	13		YC053-YC058
0027	22		PA		20-10	34-51-41	TB0608X	B001	1A		D01817	13		YC059-YR328
0028	22		CQ		23-9	22-18-11	D00624		36		D45237J	B08		YC051-YC052
0028	22		CQ		23-8	22-18-11	D00624		36		D45237J	B08		YC053-YC058
0028	22		CQ		23-7	22-18-11	D00624		36		D45237J	B08		YC059-YR328
0029	24		PK		24-1	31-62-25	D45237J		B07		D01817	54		YC051-YC052
0029	24		PK		23-10	31-62-25	D45237J		B07		D01817	54		YC053-YC058
0029	24		PK		23-11	31-62-25	D45237J		B07		D01817	54		YC059-YR328
0030	22		PA		2-9	31-62-25	D01817		53		GD00505	DC..	1A	YC051-YC052
0030	22		PA		2-7	31-62-25	D01817		53		GD00515	DC..	1A	YC053-YR328
0031	20		PA		4-10	34-16-21	D00483		4		GD00509	DC..	1A	YC051-YC052
0031	20		PA		4-9	34-16-21	D00483		4		GD00509	DC..	1A	YC053-YC057
0031	20		PA		7-2	34-16-21	D00483		4		GD00509	DC..	1A	YC058
0031	20		PA		7-5	34-16-21	D00483		4		GD00509	DC..	1A	YC059-YC064
0031	20		PA		7-6	34-16-21	D00483		4		GD00509	DC..	1A	YC065-YR328
0032	22		PA		22-8	34-16-21	D00483		6		D45237J	A20		YC051-YC052
0032	22		PA		22-7	34-16-21	D00483		6		D45237J	A20		YC053-YR328
0033	22		CQ		23-9	22-13-11	D45237J		B19		D00624	38		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W2130

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W2135	286A2135				P5, E5-2 (continued)											
0033	22		CQ		23-8	22-13-11		D45237J	B19			D00624	38			YC053-YC058
0033	22		CQ		23-7	22-13-11		D45237J	B19			D00624	38			YC059-YR328
0034	22		PA		24-11	SPARE		D45237J	B20			D01817	CAP	Y		YC051-YC058
0034	22		PA		24-2	SPARE		D45237J	B20			D01817	CAP	Y		YC059-YC064
0034	22		PA		23-11	SPARE		D45237J	B20			D01817	CAP	Y		YC065-YR328
0037	22		PA		3-8	34-21-21		D02183	3			TB0501Y	B013	1A		YC051-YC052, YC059-YR328
0037	22		PA		3-5	34-21-21		D02183	3			TB0501Y	B013	1A		YC053-YC058
0038	22		PA		21-9	34-21-21		D45237J	A04			TB0501Y	B013	1A		YC051-YC052, YC065-YR328
0038	22		PA		21-6	34-21-21		D45237J	A04			TB0501Y	B013	1A		YC053-YC064
0039	22		PA		3-8	34-21-21		D02183	10			TB0501Y	B013	1A		YC051-YC052, YC059-YR328
0039	22		PA		3-5	34-21-21		D02183	10			TB0501Y	B013	1A		YC053-YC058
0040	22		PA		22-10	34-21-21		D02183	4			D45237J	A05			YC051-YC052
0040	22		PA		22-8	34-21-21		D02183	4			D45237J	A05			YC053-YC058
0040	22		PA		22-9	34-21-21		D02183	4			D45237J	A05			YC059-YR328
0045	24		PK		12-6	34-61-18		D40623P	18			D45067J	B01			YC059-YC064
0045	24		PK		12-8	34-61-18		D40623P	18			D45067J	B01			YC065-YR328
0046	24		PK		12-6	34-61-26		D40623P	23			D45067J	A01			YC059-YC064
0046	24		PK		12-8	34-61-26		D40623P	23			D45067J	A01			YC065-YR328
0047	24		PK		12-6	22-11-53		D40623P	28			D45067J	A05			YC059-YC064
0047	24		PK		12-8	22-11-53		D40623P	28			D45067J	A05			YC065-YR328
0048	24		PK		12-6	22-11-53		D40623P	29			D45067J	A06			YC059-YC064
0048	24		PK		12-8	22-11-53		D40623P	29			D45067J	A06			YC065-YR328
0049	24		PK		12-6	22-11-53		D40623P	30			D45067J	A07			YC059-YC064
0049	24		PK		12-8	22-11-53		D40623P	30			D45067J	A07			YC065-YR328
0060	22		PA		17-1	34-58-11		D40623P	22			D02171	19			YD160-YR328
0061	22		PA		17-2	34-58-11		D40623P	21			D02173	24			YD160-YR328
2501B	24	Y2	AA		22-10	34-21-21		D02183	25			D45237J	A03			YC051-YC052
2501B	24	Y2	AA		22-8	34-21-21		D02183	25			D45237J	A03			YC053-YC058
2501B	24	Y2	AA		22-9	34-21-21		D02183	25			D45237J	A03			YC059-YR328
2501R	24	Y2	AA		0-0	34-21-21		D02183	24			D45237J	A02			ALL
2501Z			AA		0-0	34-21-21		D02183	DED			D45237J	PERG	1F		ALL
2502B	22	X2	AB		22-10	34-21-23		D02183	27			D45237J	B10			YC051-YC052
2502B	22	X2	AB		22-8	34-21-23		D02183	27			D45237J	B10			YC053-YC058
2502B	22	X2	AB		22-9	34-21-23		D02183	27			D45237J	B10			YC059-YR328
2502R	22	X2	AB		0-0	34-21-23		D02183	26			D45237J	B09			ALL
2502Z			AB		0-0	34-21-23		D02183	DED			D45237J	PERG	1F		ALL

WIRE LIST

D280A108

91-21-11

Section W2130

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2135		286A2135			P5, E5-2 (continued)											
2503B		24		Y2	AC	12-5	31-62-25	D40623P		7		D45237J	B12			YC051-YC064
2503B		24		Y2	AC	12-6	31-62-25	D40623P		7		D45237J	B12			YC065-YR328
2503R		24		Y2	AC	0-0	31-62-25	D40623P		6		D45237J	B11			ALL
2503Z					AC	0-0	31-62-25	D40623P		S/R		D45237J	PERG	1F		ALL
2504B		24		Y2	AD	12-5	34-58-21	D45237J		B16		D40623P		10		YC051-YC064
2504B		24		Y2	AD	12-6	34-58-21	D45237J		B16		D40623P		10		YC065-YR328
2504R		24		Y2	AD	0-0	34-58-21	D45237J		B15		D40623P		9		ALL
2504Z					AD	0-0	34-58-21	D45237J		PERG	1F	D40623P		S/R		ALL
2505B		24		Y2	AE	12-5	34-58-21	D45237J		B18		D40623P		12		YC051-YC064
2505B		24		Y2	AE	12-6	34-58-21	D45237J		B18		D40623P		12		YC065-YR328
2505R		24		Y2	AE	0-0	34-58-21	D45237J		B17		D40623P		11		ALL
2505Z					AE	0-0	34-58-21	D45237J		PERG	1F	D40623P		S/R		ALL
2508B		24		Y2	AH	12-6	34-61-18	D40623P		20		D45067J	B03			YC059-YC064
2508B		24		Y2	AH	12-8	34-61-18	D40623P		20		D45067J	B03			YC065-YR328
2508R		24		Y2	AH	0-0	34-61-18	D40623P		19		D45067J	A03			YC059-YR328
2508Z					AH	0-0	34-61-18	D40623P		S/R		D45067J	PERG	1F		YC059-YR328
2509B		24		Y2	AI	12-6	34-61-26	D40623P		25		D45067J	B02			YC059-YC064
2509B		24		Y2	AI	12-8	34-61-26	D40623P		25		D45067J	B02			YC065-YR328
2509R		24		Y2	AI	0-0	34-61-26	D40623P		24		D45067J	A02			YC059-YR328
2509Z					AI	0-0	34-61-26	D40623P		S/R		D45067J	PERG	1F		YC059-YR328
2510B		22		X2	AJ	12-5	31-32-15	D40623P		17		D45237J	A19			YC059-YC064
2510B		22		X2	AJ	12-6	31-32-15	D40623P		17		D45237J	A19			YC065-YR328
2510R		22		X2	AJ	0-0	31-32-15	D40623P		16		D45237J	A15			YC059-YR328
2510Z					AJ	0-0	31-32-15	D40623P		S/R		D45237J	PERG	1F		YC059-YR328
2511B		24		Y2	AK	12-6	22-11-53	D40623P		27		D45067J	B04			YC059-YC064
2511B		24		Y2	AK	12-8	22-11-53	D40623P		27		D45067J	B04			YC065-YR328
2511R		24		Y2	AK	0-0	22-11-53	D40623P		26		D45067J	A04			YC059-YR328
2511Z					AK	0-0	22-11-53	D40623P		S/R		D45067J	PERG	1F		YC059-YR328
W2136		286A2136			P91 TO P6 AND P18											
0001		08		CQ		21-2	24-61-21	D11424		A		TB5180C	4	E		YC051-YC055
0001		08		CQ		21-1	24-61-21	D11424		A		TB5180C	4	E		YC056-YD158
0001		08		CQ		21-4	24-61-21	D11424		A		TB5180C	4	E		YD160-YR328
0002		10		CQ		25-8	24-61-22	D11424		C		TB5060H	5	E		YC051-YC055
0002		10		CQ		25-7	24-61-22	D11424		C		TB5060H	5	E		YC056-YD158
0002		10		CQ		25-9	24-61-22	D11424		C		TB5060H	5	E		YD160-YR328
0003		08		CQ		25-8	24-34-11	D11424		E		TB5060H	4	E		YC051-YC055
0003		08		CQ		25-7	24-34-11	D11424		E		TB5060H	4	E		YC056-YD158
0003		08		CQ		25-9	24-34-11	D11424		E		TB5060H	4	E		YD160-YR328

WIRE LIST

D280A108

91-21-11

Section W2130

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I W2138	286A2138			AP0600B TO AE0201A (LA1)											
I 5501	12	PA		25-1	30-41-11	D41430P		1			D41432P	1			YC051-YC055
I 5501	12	PA		25-3	30-41-11	D41430P		1			D41432P	1			YC056-YR328
I 5502	16	PA		25-1	30-41-11	D41430P		2			D41432P	2			YC051-YC055
I 5502	16	PA		25-3	30-41-11	D41430P		2			D41432P	2			YC056-YR328
I 5503	16	HA		25-1	SPARE	D41430P		3			D41432P	3			YC051-YC055
I 5503	16	HA		25-3	SPARE	D41430P		3			D41432P	3			YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W2130

Page 6 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2149	286A2149			CAPTAINS NAV ELEX PANEL TO E/E BAY											
0004	22		PA		16-1	34-55-11	D00303				4				YC051-YD158, YL951-YR328
0011	22		CQ		3-8	34-51-11	D00263				11				YC051-YD158, YL951-YR328
0012	22		CQ		16-1	34-51-41	D00303				12				YC051-YD158, YL951-YR328
0013	22		PA		15-0	34-55-11	D40095P				A03				YC051-YD158, YL951-YR328
0014	22		CQ		3-8	34-51-11	D00263				36				YL951-YR328
0015	22		CQ		9-7	34-51-41	D00263				15				YC051-YD158, YL951-YR328
0022	22		PA		15-0	34-53-11	D40095P				A02				YC051-YD158, YL951-YR328
0023	22		PA		16-6	SPARE	D00263		CAP	Y					YC051-YD158, YL951-YR328
0025	22		PA		16-4	23-51-51	D00263				5				YC051-YD158, YL951-YR328
0026	22		PA		16-1	34-55-11	D00303				26				YC051-YD158, YL951-YR328
0027	22		PA		16-1	SPARE	D00303		CAP	Y					YC051-YD158, YL951-YR328
0028	20		CQ		3-8	34-51-41	D00263				28				YC051-YD158, YL951-YR328
0030	22		PA		16-1	34-55-11	D00303				30				YC051-YD158, YL951-YR328
0031	22		CQ		16-4	34-51-41	D00263				31				YC051-YD158, YL951-YR328
0032	22		PA		16-4	34-51-41	D00263				46				YL951-YR328
0033	22		PA		16-4	34-51-41	D00263				40				YL951-YR328
0035	22		PA		9-7	34-55-11	D00263				35				YC051-YD158, YL951-YR328
0037	22		PA		16-1	34-55-11	D00303				37				YC051-YD158, YL951-YR328
0038	22		CQ		16-4	34-51-41	D00263				38				YC051-YD158, YL951-YR328
0042	20		CQ		3-6	34-51-11	D00303				42				YC051-YD158, YL951-YR328
0045	22		PA		16-1	22-11-18	D00303				45				YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W2140

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Fam	Description FT-IN Diagram		From	Term	Type	Splice	To	Term	Type	Splice	Effectivity
						Equip	Equip								
W2149	286A2149				CAPTAINS NAV ELEX PANEL TO E/E BAY (continued)										
0046	22	PA			16-1 34-55-11	D00303		46			D04029J	6			YC051-YD158, YL951-YR328
0048	22	CQ			3-8 34-51-11	D00263		48			GD00801	DC..	1A		YC051-YD158, YL951-YR328
0049	20	CQ			4-0 33-18-61	D00303		49			TB0803Y	B015	1A		YC051-YC064, YC067-YC068
0049	20	CQ			4-0 33-18-61	D00303		49			TB0804Z	A017	1A		YC065
0049	20	CQ			4-5 33-18-61	D00303		49			TB0804Z	A017	1A		YC070-YD158, YL951-YR328
0050	20	CQ			4-2 33-11-33	D00303		50			TB0801W	B021	1		YC051-YD158, YL951-YR328
0051	22	CQ			16-4 34-51-41	D00263		51			D04029J	51			YC051-YD158, YL951-YR328
0052	20	CQ			3-9 33-11-33	D00303		52			GD00805	AC..	1A		YC051-YD158, YL951-YR328
0053	22	PA			16-1 34-55-11	D00303		53			D04029J	3			YC051-YD158, YL951-YR328
0054	22	CQ			16-1 34-51-11	D00303		54			D04029J	54			YC051-YD158, YL951-YR328
0055	20	CQ			3-6 34-51-11	D00303		55			GD00811	AC..	1A		YC051-YD158, YL951-YR328
2001B	24	Y2	AA		16-1 34-31-11	D00303		29			D04029J	29			YC051-YD158, YL951-YR328
2001R	24	Y2	AA		0-0 34-31-11	D00303		28			D04029J	28			YC051-YD158, YL951-YR328
2001Z			AA		0-0 34-31-11	D00303		S/R			D04029J	S/R			YC051-YD158, YL951-YR328
2002B	24	Y2	AB		16-4 34-51-11	D00263		21			D04029J	21			YC051-YD158, YL951-YR328
2002R	24	Y2	AB		0-0 34-51-11	D00263		20			D04029J	20			YC051-YD158, YL951-YR328
2002Z			AB		0-0 34-51-11	D00263		S/R			D04029J	S/R			YC051-YD158, YL951-YR328
2003B	24	Y2	AC		16-1 34-55-11	D00303		25			D04029J	25			YC051-YD158, YL951-YR328
2003R	24	Y2	AC		0-0 34-55-11	D00303		24			D04029J	24			YC051-YD158, YL951-YR328
2003Z			AC		0-0 34-55-11	D00303		S/R			D04029J	S/R			YC051-YD158, YL951-YR328

WIRE LIST
D280A108

91-21-11
Section W2140
Page 2
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2149	286A2149			CAPTAINS NAV ELEX PANEL TO E/E BAY (continued)											
2004B	24	Y2	AD		16-4	22-11-51	D00263	18	VP		D04029J	18			YC051-YD158, YL951-YR328
2004R	24	Y2	AD		0-0	22-11-51	D00263	17	VP		D04029J	17			YC051-YD158, YL951-YR328
2004Z			AD		0-0	22-11-51	D00263	DED			D04029J	S/R			YC051-YD158, YL951-YR328
2005B	24	Y2	AE		16-3	SPARE	D00303	CAP	Y		D04029J	34			YC051-YD158, YL951-YR328
2005R	24	Y2	AE		0-0	SPARE	D00303	CAP	Y		D04029J	33			YC051-YD158, YL951-YR328
2005Z			AE		0-0	SPARE	D00303	S/R			D04029J	S/R			YC051-YD158, YL951-YR328
2006B	24	Y2	AF		16-6	SPARE	D00263	CAP	Y		D04029J	36			YC051-YD158, YL951-YR328
2006R	24	Y2	AF		0-0	SPARE	D00263	CAP	Y		D04029J	35			YC051-YD158, YL951-YR328
2006Z			AF		0-0	SPARE	D00263	S/R			D04029J	S/R			YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W2140

Page 3 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2151	286A2151			F/O'S NAV ELEX PANEL TO E/E BAY											
0004	22		PA		14-8	34-55-21	D00305		4		D04031J		4		YC051-YD158, YL951-YR328
0011	22		PA		3-4	34-51-21	D00265		11		GD00803	DC..	1A		YC051-YD158, YL951-YR328
0012	22		PA		14-8	34-51-41	D00305		12		D04031J		12		YC051-YD158, YL951-YR328
0013	22		PA		16-10	34-55-21	TB0606Y	A005	1A		D04031J		13		YC051-YD158, YL951-YR328
0014	22		PA		3-4	34-51-21	D00265		36		GD00803	DC..	1A		YL951-YR328
0015	22		PA		12-2	34-51-41	D00265		15		TB0608X	B001	1A		YC051-YD158, YL951-YR328
0023	22		PA		14-6	SPARE	D00265	CAP	Y		D04031J		23		YC051-YD158, YL951-YR328
0025	22		PA		14-6	23-51-51	D00265		5		D04031J		15		YC051-YD158, YL951-YR328
0026	22		PA		14-8	34-55-21	D00305		26		D04031J		26		YC051-YD158, YL951-YR328
0027	22		PA		14-8	SPARE	D00305	CAP	Y		D04031J		27		YC051-YD158, YL951-YR328
0028	20		PA		3-4	34-51-41	D00265		28		GD00803	DC..	1A		YC051-YD158, YL951-YR328
0030	22		PA		14-8	34-55-21	D00305		30		D04031J		30		YC051-YD158, YL951-YR328
0031	22		PA		14-6	34-51-41	D00265		31		D04031J		31		YC051-YD158, YL951-YR328
0032	22		PA		14-6	34-51-41	D00265		46		D04031J		10		YL951-YR328
0033	22		PA		14-6	34-51-41	D00265		40		D04031J		11		YL951-YR328
0035	22		PA		12-2	34-55-21	D00265		35		TB0606Y	A005	1A		YC051-YD158, YL951-YR328
0037	22		PA		14-8	34-55-21	D00305		37		D04031J		37		YC051-YD158, YL951-YR328
0038	22		PA		14-6	34-51-41	D00265		38		D04031J		38		YC051-YD158, YL951-YR328
0042	20		PA		3-7	34-51-21	D00305		42		GD00811	ST..	1A		YC051-YD158, YL951-YR328
0045	22		PA		14-8	22-11-18	D00305		45		D04031J		5		YC051-YD158, YL951-YR328
0046	22		PA		14-8	34-55-21	D00305		46		D04031J		6		YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W2150

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2151	286A2151			F/O'S NAV ELEX PANEL TO E/E BAY (continued)											
0048	22		PA		3-4	34-51-21	D00265	48			GD00803	DC..	1A		YC051-YD158, YL951-YR328
0049	20		CQ		3-10	33-18-61	D00305	49			TB0803Y	B015	1A		YC051-YD158, YL951-YR328
0050	20		CQ		3-4	33-11-41	D00305	50			TB0801W	A021	1		YC051-YD158, YL951-YR328
0051	22		PA		14-6	34-51-41	D00265	51			D04031J	51			YC051-YD158, YL951-YR328
0052	20		CQ		3-5	33-11-41	D00305	52			GD00805	AC..	1A		YC051-YD158, YL951-YR328
0053	22		PA		14-8	34-55-21	D00305	53			D04031J	3			YC051-YD158, YL951-YR328
0054	22		PA		14-8	34-51-21	D00305	54			D04031J	54			YC051-YD158, YL951-YR328
0055	20		PA		3-7	34-51-21	D00305	55			GD00811	AC..	1A		YC051-YD158, YL951-YR328
2001B	24		Y2	AA	14-8	34-31-21	D00305	29			D04031J	29			YC051-YD158, YL951-YR328
2001R	24		Y2	AA	0-0	34-31-21	D00305	28			D04031J	28			YC051-YD158, YL951-YR328
2001Z				AA	0-0	34-31-21	D00305	S/R			D04031J	S/R			YC051-YD158, YL951-YR328
2002B	24		Y2	AB	14-6	34-51-21	D00265	21			D04031J	21			YC051-YD158, YL951-YR328
2002R	24		Y2	AB	0-0	34-51-21	D00265	20			D04031J	20			YC051-YD158, YL951-YR328
2002Z				AB	0-0	34-51-21	D00265	S/R			D04031J	S/R			YC051-YD158, YL951-YR328
2003B	24		Y2	AC	14-8	34-55-21	D00305	25			D04031J	25			YC051-YD158, YL951-YR328
2003R	24		Y2	AC	0-0	34-55-21	D00305	24			D04031J	24			YC051-YD158, YL951-YR328
2003Z				AC	0-0	34-55-21	D00305	S/R			D04031J	S/R			YC051-YD158, YL951-YR328
2004B	24		Y2	AD	14-6	22-11-51	D00265	18	VP		D04031J	18			YC051-YD158, YL951-YR328
2004R	24		Y2	AD	0-0	22-11-51	D00265	17	VP		D04031J	17			YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W2150

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2151	286A2151			F/O'S NAV ELEX PANEL TO E/E BAY (continued)											
2004Z				AD	0-0	22-11-51	D00265	DED			D04031J	S/R			YC051-YD158, YL951-YR328
2005B	24	Y2	AE		14-8	SPARE	D00305	CAP	Y		D04031J	34			YC051-YD158, YL951-YR328
2005R	24	Y2	AE		0-0	SPARE	D00305	CAP	Y		D04031J	33			YC051-YD158, YL951-YR328
2005Z				AE	0-0	SPARE	D00305	S/R			D04031J	S/R			YC051-YD158, YL951-YR328
2006B	24	Y2	AF		14-8	SPARE	D00265	CAP	Y		D04031J	36			YC051-YD158, YL951-YR328
2006R	24	Y2	AF		0-0	SPARE	D00265	CAP	Y		D04031J	35			YC051-YD158, YL951-YR328
2006Z				AF	0-0	SPARE	D00265	S/R			D04031J	S/R			YC051-YD158, YL951-YR328

WIRE LIST
D280A108

91-21-11
Section W2150
Page 3 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2169	286A2169			RIGHT DC ELEX PWR FROM P6 TO E3.											
0001	20	PA		22-1	SPARE	D46063P		1			D46035P	1			ALL
0002	22	PA		22-1	SPARE	D46063P		2			D46035P	2			ALL
0003	20	PA		22-1	SPARE	D46063P		3			D46035P	3			ALL
0004	22	PA		22-10	SPARE	D46063P		4			D46043P	4			ALL
0005	22	PA		22-10	27-32-21	D46063P		5			D46043P	5			ALL
0006	22	PA		22-10	27-32-21	D46063P		6			D46043P	6			ALL
0007	22	PA		22-10	SPARE	D46063P		7			D46043P	7			ALL
0008	22	PA		22-10	SPARE	D46063P		8			D46043P	8			ALL
0009	20	PA		22-1	27-62-41	D46063P		9			SM00650		W		YC051-YC065
0009	20	PA		22-1	SPARE	D46063P		9			D46035P	9			YC067-YR328
0010	20	PA		22-1	27-62-41	D46063P		10			SM00651		W		YC051-YC065
0010	20	PA		22-1	SPARE	D46063P		10			D46035P	5			YC067-YR328
0011	20	PA		22-10	27-62-41	D46063P		11			D46043P	11			YC051-YC065
0011	20	PA		22-10	SPARE	D46063P		11			D46043P	11			YC067-YR328
0012	20	CQ		22-10	27-25-11	D46063P		12			D46043P		CAP	Y	YC051-YD153
0012	20	CQ		22-10	27-25-11	D46063P		12			D46043P	12			YD154-YD155
0012	20	CQ		22-10	SPARE	D46063P		12			D46043P	12			YD157-YR328
0013	20	GA		1-0	27-62-41	D46043P		9			SM00650		W		YC051-YC055
0013	20	PA		1-0	27-62-41	D46043P		9			SM00650		W		YC056-YC065
0014	20	GA		1-0	27-62-41	D46043P		10			SM00651		W		YC051-YC055
0014	20	PA		1-0	27-62-41	D46043P		10			SM00651		W		YC056-YC065
0015	16	CQ		22-1	31-62-21	D46063P		15			D46035P	4			ALL
0019	16	PA		22-1	31-62-21	D46063P		19			D46035P	7			ALL
0023	16	CQ		22-1	31-62-11	D46063P		23			D46035P	10			ALL
0046	20	PA		22-10	27-62-41	D46043P		1			D46063P	16			YN231-YN501
0047	20	PA		22-10	27-62-41	D46043P		2			D46063P	17			YN231-YN501
0048	20	PA		22-10	27-62-41	D46043P		3			D46063P	18			YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W2160

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2175	286A2175			LEFT DC ELEX PWR FROM P18 TO E1.											
0001	20		CQ		10-11	22-11-11	D41803P		1		D41821P	A01			ALL
0002	20		CQ		10-11	22-11-12	D41803P		2		D41821P	A02			ALL
0003	20		CQ		10-11	22-11-12	D41803P		3		D41821P	A03			ALL
0004	20		CQ		10-11	22-18-11	D41803P		4		D41821P	A04			ALL
0005	22		PA		10-11	27-32-11	D41803P		5		D41821P	A05			ALL
0006	22		PA		10-11	SPARE	D41803P		6		D41821P	A06			ALL
0007	20		PA		10-11	22-23-11	D41803P		7		D41821P	A07			ALL
0008	20		PA		10-11	SPARE	D41803P		8		D41821P	A08			ALL
0009	22		PA		10-11	SPARE	D41803P		9		D41821P	A09			ALL
0010	22		PA		10-11	SPARE	D41803P		10		D41821P	A10			ALL
0011	20		PA		10-11	34-61-22	D41803P		11		D41821P	B01			ALL
0012	20		PA		10-11	SPARE	D41803P		12		D41821P	B02			YL951-YR328
0013	20		PA		10-11	SPARE	D41803P		13		D41821P	B03			ALL
0014	18		PA		10-11	22-31-11	D41803P		14		D41821P	F			YC051-YD155
0014	18		PA		10-11	22-31-31	D41803P		14		D41821P	F			YD157-YR328
0015	20		PA		10-11	SPARE	D41803P		15		D41821P	B05			ALL
0016	16		PA		9-8	SPARE	D41803P		16		D41823P	4			ALL
0017	20		PA		10-11	SPARE	D41803P		17		D41821P	B07			ALL
0018	16		PA		9-8	SPARE	D41803P		18		D41823P	7			YC051-YD155
0018	18		PA		10-11	22-11-11	D41803P		18		D41821P	K			YD157-YR328
0019	20		PA		9-8	SPARE	D41803P		19		D41823P	9			ALL
0020	16		PA		9-8	SPARE	D41803P		20		D41823P	10			ALL
0021	20		PA		9-8	SPARE	D41803P		21		D41823P	1			ALL
0022	16		CQ		10-11	34-21-11	D41803P		22		D41821P	H			ALL
0023	20		PA		9-8	SPARE	D41803P		23		D41823P	3			ALL
0024	16		PA		10-11	SPARE	D41803P		24		D41821P	G			YC051-YC061
0024	16		PA		10-11	SPARE	D41803P	CAP	Y		D41821P	G			YC062-YR328
0025	20		PA		9-8	SPARE	D41803P		25		D41823P	5			ALL
0026	10		CQ		3-10	30-42-11	D41803P		24	10	SP01084		9		YC062-YR328
W2177	286A2177			DUAL ATC ELEC PNL TO E1-2											
0001	20		CQ		4-10	33-11-33	D00211		1		TB0801W	A005	1		YC051-YC052
0001	20		CQ		5-0	33-11-33	D00211		1		TB0801W	A005	1		YC053-YC057
0001	20		CQ		5-0	33-11-33	D00211		1		TB0801W	B021	1		YC058-YD157
0001	20		CQ		5-0	33-11-33	D00211		1		TB0801V	B011	1		YD158-YN236, YN501-YR328
0002	20		CQ		4-9	33-11-33	D00211		2		GD00805	AC..	1A		YC051-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W2170

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2177		286A2177				DUAL ATC ELEC PNL TO E1-2 (continued)										
0003		20		CQ		17-4	34-53-11	D00211	3			D41217J	3			YC051-YN236, YN501-YR328
0004		20		PA		4-5	34-53-11	D00211	4			GD00811	AC..	1A		YC051-YN236, YN501-YR328
0005		20		PA		17-4	34-53-11	D00211	5	VP		D41217J	5			YC051-YN236, YN501-YR328
0006		20		PA		4-5	34-53-11	D00211	6			GD00801	DC..	1A		YC051-YN236, YN501-YR328
0007		24		PK		11-2	34-53-11	D00211	7			TB1806Y	A009	1A		YC051-YC052
0007		24		PK		17-4	34-53-11	D00211	7			D41217J	7			YC053-YN236, YN501-YR328
0008		20		PA		4-5	34-53-11	D00211	8			GD00811	DC..	1A		YC051-YN236, YN501-YR301, YR312-YR328
0008		20		PA		4-5	34-53-11	D00211			FL	GD00811	DC..	1A		YR303-YR309
0009		20		PA		17-4	34-53-11	D00211	9	VP		D41217J	9			YC051-YN236, YN501-YR328
0010		20		PA		17-4	34-53-11	D00211	10	VP		D41217J	10			YC051-YN236, YN501-YR328
0011		24		PK		17-4	34-53-11	D00211	11			D41217J	11			YC051-YN236, YN501-YR328
0012		24		PK		17-4	34-53-11	D00211	12			D41217J	12			YC051-YN236, YN501-YR328
0015		24		PK		17-4	34-53-11	D00211	15			D41217J	15			YC051-YN236, YN501-YR328
0016		24		PK		17-4	34-53-11	D00211	16			D41217J	6			YC051-YN236, YN501-YR328
0018		20		CQ		4-10	33-18-61	D00211	18			TB0803Z	A005	1A		YC051-YN236, YN501-YR328
0020		24		PK		17-4	34-53-11	D00211	20			D41217J	1			YC051-YN236, YN501-YR328
0021		20		CQ		4-10	33-18-61	D00211	21			TB0803Z	B005	1A		YC051-YN236, YN501-YR328
0024		24		PK		17-4	34-53-11	D00211	24			D41217J	2			YC051-YN236, YN501-YR328
0028		20		PA		4-5	34-53-11	D00211			FL	GD00801	ST..	1A		YR312-YR328
0037		24		PK		16-1	34-53-11	D41217J	7			TB1806Y	A009	1A		YC051-YC052
2001B		24		Y2	AA	17-4	34-53-11	D00211	23			D41217J	14			YC051-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W2170

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2177	286A2177			DUAL ATC ELEC PNL TO E1-2 (continued)											
2001R	24	Y2		AA	0-0	34-53-11	D00211	22			D41217J	13			YC051-YN236, YN501-YR328
2001Z				AA	0-0	34-53-11	D00211	DED			D41217J	S/R			YC051-YN236, YN501-YR301
2001Z				AA	0-0	34-53-11	D00211			FL	D41217J	S/R			YR303-YR328
FRQQ					0-0	34-53-11	D00211			FL	D00211	8			YR303-YR309

WIRE LIST
D280A108

91-21-11
Section W2170
Page 3 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To					
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
I	W2201	286A2201				LEFT AC ELEX PWR FROM P18 TO E3.										
	0001	20	PA		23-1	SPARE	D41805P		1			D41817P		1		YC051-YC055
I	0001	20	PA		23-6	SPARE	D41805P		1			D41817P		1		YC056-YR328
	0002	20	PA		23-1	SPARE	D41805P		2			D41817P		2		YC051-YC055
I	0002	20	PA		23-6	SPARE	D41805P		2			D41817P		2		YC056-YR328
	0003	20	PA		23-1	SPARE	D41805P		3			D41817P		3		YC051-YC055
I	0003	20	PA		23-6	SPARE	D41805P		3			D41817P		3		YC056-YR328
	0004	22	PA		23-1	34-33-11	D41805P		4			D41817P		8		YC051-YC055
I	0004	22	PA		23-6	34-33-11	D41805P		4			D41817P		8		YC056-YR328
	0005	20	PA		23-0	22-23-12	D41805P		5			D41819P		5		YC051-YC055
I	0005	20	PA		23-5	22-23-12	D41805P		5			D41819P		5		YC056-YR328
	0006	22	CQ		23-0	31-31-14	D41805P		6			D41819P		6		YC051-YC055
I	0006	22	CQ		23-5	31-31-14	D41805P		6			D41819P		6		YC056-YR328
I	0007	22	CQ		9-3	31-31-11	D41805P		7			TB1808Y	B009	1A		ALL
	0008	20	PA		23-0	SPARE	D41805P		8			D41819P		8		YC051-YC055
I	0008	20	PA		23-5	SPARE	D41805P		8			D41819P		8		YC056-YD170
	0008	20	PA		23-5	SPARE	D41805P		8	VP		D41819P		8		YL951-YL968, YN231-YN235
	0009	20	PA		25-0	SPARE	D41805P		9			D43313P		9		YC051-YC055
	0009	20	PA		25-5	SPARE	D41805P		9			D43313P		9		YC056-YC060
	0010	20	PA		23-1	SPARE	D41805P		10			D41817P		12		YC051-YC055
I	0010	20	PA		23-6	SPARE	D41805P		10			D41817P		12		YC056-YR328
	0011	20	PA		23-1	SPARE	D41805P		11			D41817P		11		YC051-YC055
I	0011	20	PA		23-6	SPARE	D41805P		11			D41817P		11		YC056-YR328
	0012	20	PA		23-0	78-36-11	D41805P		12			D41819P		12		YC051-YC055
I	0012	20	PA		23-5	78-36-11	D41805P		12			D41819P		12		YC056-YR328
	0013	20	PA		23-0	SPARE	D41805P		13			D41819P		13		YC051-YC055
I	0013	20	PA		23-5	SPARE	D41805P		13			D41819P		13		YC056-YR328
	0014	20	PA		23-0	SPARE	D41805P		14			D41819P		14		YC051-YC055
	0014	20	PA		23-5	SPARE	D41805P		14			D41819P		14		YC056-YC060
	0015	14	PA		23-0	SPARE	D41805P		15			D41819P		15		YC051-YC055
I	0015	14	PA		23-5	SPARE	D41805P		15			D41819P		15		YC056-YD170
	0016	20	PA		23-0	SPARE	D41805P		16			D41819P		16		YC051-YC055
I	0016	20	PA		23-5	SPARE	D41805P		16			D41819P		16		YC056-YR328
	0017	20	PA		23-0	SPARE	D41805P		17			D41819P		17		YC051-YC055
I	0017	20	PA		23-5	SPARE	D41805P		17			D41819P		17		YC056-YR328
	0018	20	PA		23-0	SPARE	D41805P		18			D41819P		18		YC051-YC055
I	0018	20	PA		23-5	SPARE	D41805P		18			D41819P		18		YC056-YR328
	0019	16	PA		23-1	SPARE	D41805P		19			D41817P		4		YC051-YC055
I	0019	16	PA		23-6	SPARE	D41805P		19			D41817P		4		YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W2200

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2201		286A2201			LEFT AC ELEX PWR FROM P18 TO E3. (continued)											
0020		20		PA		29-6	27-32-11	D41819P	20			SP00089		S		YC051-YC055
0020		20		PA		29-11	27-32-11	D41819P	20			SP00089		S		YC056-YR322
0020		20		PA		28-7	27-32-11	D41819P	20			SP00089		S		YR323-YR328
0021		20		PA		23-1	SPARE	D41805P	21			D41817P	5			YC051-YC055
0021		20		PA		23-6	SPARE	D41805P	21			D41817P	5			YC056-YR328
0022		22		PA		25-0	SPARE	D41805P	22			D43313P	12			YC051-YC055
0022		22		PA		25-5	SPARE	D41805P	22			D43313P	12			YC056-YD157
0022		22		PA		25-5	23-27-31	D41805P	22			D43313P	12			YD158-YR328
0023		16		PA		25-0	SPARE	D41805P	23			D43313P	4			YC051-YC055
0023		16		PA		25-5	SPARE	D41805P	23			D43313P	4			YC056-YD170, YN501
0023		22		PA		25-5	SPARE	D41805P	23			D43313P	4			YL951-YN260
0024		20		PA		25-0	SPARE	D41805P	24			D43313P	2			YC051-YC055
0024		20		PA		25-5	SPARE	D41805P	24			D43313P	2			YC056-YD170, YN501
0024		22		PA		25-5	SPARE	D41805P	24			D43313P	2			YL951-YN260
0025		22		PA		25-0	23-27-13	D41805P	25			D43313P	5			YC051-YC055
0025		22		PA		25-5	23-27-13	D41805P	25			D43313P	5			YC056-YD157
0025		22		PA		25-5	SPARE	D41805P	25			D43313P	5			YD158-YN501
0026		22		PA		25-0	23-27-11	D41805P	26			D43313P	6			YC051-YC055
0026		22		PA		25-5	23-27-11	D41805P	26			D43313P	6			YC056-YD157
0026		22		PA		25-5	SPARE	D41805P	26			D43313P	6			YD158-YR328
0027		16		PA		25-0	SPARE	D41805P	27			D43313P	7			YC051-YC055
0027		16		PA		25-5	SPARE	D41805P	27			D43313P	7			YC056-YD170, YN501
0027		22		PA		25-5	SPARE	D41805P	27			D43313P	7			YL951-YN260
0028		20		PA		25-0	SPARE	D41805P	28			D43313P	8			YC051-YC055
0028		20		PA		25-5	SPARE	D41805P	28	VP		D43313P	8			YC056-YD170
0028		22		PA		25-5	SPARE	D41805P	28	VP		D43313P	8			YL951-YN260
0028		20		PA		25-5	SPARE	D41805P	28	VP		D43313P	8			YN501
0030		20		PA		25-5	23-32-21	D41805P	20			D43313P	3			YL951-YL967, YN231-YN235 YL968-YL999, YN236-YN260
0030		20		PA		25-5	SPARE	D41805P	20			D43313P	3			
W2204		286A2204			P6 (R CAB CEILING) DISC TO R CONTROL CABIN AREA (RN2)											
5502		18		PA		19-8	33-14-12	SP00438		S		TB0262V	A013	1		YC051-YC052
5502		18		PA		19-9	33-14-12	SP00438		S		TB0262V	A013	1		YC053-YC055
5502		18		PA		20-8	33-14-12	SP00438		S		TB0262V	A013	1		YC056-YR328
5503		18		PA		3-9	33-14-12	L00414	=G	C		GD01352	AC..	E		YC051-YC052
5503		18		PA		3-11	33-14-12	L00414	=G	C		GD01352	AC..	E		YC053-YR328
5504		18		PA		11-4	33-14-12	L00413	=P	C		SP00438		S		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W2200

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2204		286A2204			P6 (R CAB CEILING) DISC TO R CONTROL CABIN AREA (RN2) (continued)											
5504		18		PA		11-6	33-14-12	L00413	=P	C		SP00438		S		YC053-YR328
5506		18		PA		25-3	33-14-12	L00412	=P	C		SP00438		S		YC051-YC052
5506		18		PA		25-6	33-14-12	L00412	=P	C		SP00438		S		YC053-YR328
5507		18		PA		3-5	33-14-12	L00412	=G	E		GD00610	AC..	E	*1	YC051-YD158
5507		18		PA		3-5	33-14-12	L00412	=G	E		GD00610	AC..	E		YD160-YR328
5508		20		PA		17-8	33-17-11	D40582P		4		TB5020	1	E		YC051-YC052
5508		20		PA		17-9	33-17-11	D40582P		4		TB5020	1	E		YC053-YR328
5509		20		PA		2-8	33-17-11	SM00002			S	D00798	4			ALL
5510		20		PA		2-8	33-17-11	L01004	=G	C		GD00610	AC..	E		ALL
5511		20		PA		24-10	33-17-11	D00798		12		L01004	=P	C		ALL
5512		20		PA		5-4	33-11-21	D00798		1		SP02140		S		ALL
5513		20		PA		2-10	33-11-21	D00798		2		GD03316	AC..	E		ALL
5514		20		PA		2-8	33-17-11	SM00002			S	D00798	11			ALL
5515		20		PA		11-11	30-41-12	S00191	=B	B	*	D40582P	7			YC051-YC052
5515		20		PA		12-1	30-41-12	S00191	=B	B	*	D40582P	7			YC053-YD158
5516		20		PA		2-2	30-41-12	S00191	=A	B		A00012	=A	E		YC051-YD158
5517		20		PA		25-1	33-17-11	D00798		10		SP00608		S		ALL
5518		20		PA		5-5	30-41-12	A00012	=B	E		A00011	=A	E		YC051-YD158
5519		20		PA		1-10	30-41-12	A00011	=B	E		GD00610	AC..	E	*1	YC051-YD158
5530		20		PA		3-4	33-17-11	SM00002			S	TB5020	1	E		ALL
5533		20		PA		13-2	33-14-11	D12110	=1			TB0805X	A013	1A		ALL
5534		20		PA		2-2	33-14-11	D12112	=1			GD00210	AC..	E		ALL
5535		20		PA		2-10	33-17-11	D00798		6		GD03316	AC..	E		ALL
5536		20		PA		27-6	30-41-12	S00191	=B	B	*	S00756	=B	B		YC051-YC052
5536		20		PA		28-9	30-41-12	S00191	=B	B	*	S00756	=B	B		YC053-YD158
5536		20		PA		20-8	30-41-12	D40582P		7		S00756	=B	B		YD160-YR328
5537		20		PA		2-7	30-41-12	A00022	=A	E		S00756	=A	B		YC051-YC052
5537		20		PA		4-2	30-41-12	A00022	=A	E		S00756	=A	B		YC053-YR328
5538		20		PA		2-2	30-41-12	A00022	=B	E		GD01296	AC..	E		YC051-YC052
5538		20		PA		2-4	30-41-12	A00022	=B	E		GD01296	AC..	E		YC053-YR328
B-BG						0-0	33-17-11	L00009	=G			GD00610	AC..	E		ALL
B-BP						0-0	33-17-11	L00009	=P			SP00608		S		ALL
D-DP						0-0	33-14-12	L00414	=P			SP00438		S		ALL
W2205		286A2205			STBY INDICATORS (RMI, SAI, ALT/SPD) TO E1-2/E1-4											
0001		20		CQ		16-5	33-11-32	D03681		1		SP02205		S		YC051-YD157
0002		20		CQ		3-5	33-11-32	D03681		2		GD00179	AC..	1A		YC051-YD157
0002		20		CQ		3-5	SPARE	D10853	CAP	Y		GD00179	AC..	1A		YD158, YL951-YR328
0003		20		CQ		16-5	33-11-32	D03679		1		SP02205		S		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W2200

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description		From				To					
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2205	286A2205			STBY INDICATORS (RMI, SAI, ALT/SPD) TO E1-2/E1-4 (continued)											
0003	20		CQ		17-5	33-11-32	D03679		1		SP02205		S		YD158, YL951-YR328
0004	20		CQ		3-5	33-11-32	D03679		2		GD00179	AC..	1A		YC051-YD158, YL951-YR328
0005	20		CQ		3-4	33-11-32	D00849		2		GD00179	AC..	1A		YC051-YD157
0005	20		CQ		3-5	SPARE	D10853	CAP	Y		GD00179	AC..	1A		YD158, YL951-YR328
0006	20		PA		3-5	34-22-11	D03679		6		GD00179	ST..	1A		YC051-YD158, YL951-YR328
0007	22		PA		11-7	34-24-11	D03681		7		SP02186		S		YC051-YD157
0007	22		PA		12-6	SPARE	D10853	CAP	Y		SP02186		S		YD158, YL951-YR328
0008	20		PA		3-5	34-24-11	D03681		8		GD00179	DC..	1A		YC051-YD157
0008	20		PA		3-5	SPARE	D10853	CAP	Y		GD00179	DC..	1A		YD158, YL951-YR328
0009	20		PA		3-4	34-21-11	D00849		5		GD00179	ST..	1A		YC051-YD157
0009	20		PA		3-5	SPARE	D10853	CAP	Y		GD00179	ST..	1A		YD158, YL951-YR328
0010	20		CQ		17-4	33-11-32	D10853		J-		SP02205		S		YD158, YL951-YR328
0011	20		CQ		3-5	33-11-32	D10853		I-		GD00179	AC..	1A		YD158, YL951-YR328
0013	20		PA		3-4	34-21-11	D00849		3		GD00179	DC..	1A		YC051-YD157
0013	20		PA		3-5	SPARE	D10853	CAP	Y		GD00179	DC..	1A		YD158, YL951-YR328
0014	20		PA		11-6	34-21-11	D00849		4		SP02085		S		YC051-YD157
0014	20		PA		12-6	SPARE	D10853	CAP	Y		SP02085		S		YD158, YL951-YR328
0015	20		CQ		16-4	33-11-32	D00849		1		SP02205		S		YC051-YD157
0016	22		PA		29-11	34-21-15	D03679		16		D04205J		7		YC051-YD158, YL951-YR328
0018	22		PA		29-11	SPARE	D03681		18	VP	D04205J		13		YC051-YD157
0020	22		PA		27-7	SPARE	D03679		5	VP	D40049J		5		YC051-YD158, YL951-YR328
0021	22		PA		27-7	SPARE	D03679		17	VP	D40049J		6		YC051-YD158, YL951-YR328
0022	22		PA		0-7	34-24-15	D10853		G		SM00001		W		YD158, YL951-YR328
0023	22		PA		0-7	34-24-15	D10853		D-		SM00001		W		YD158, YL951-YR328
0024	22		PA		0-7	34-24-15	D10853		K-		SM00001		W		YD158, YL951-YR328
0026	20		PA		3-5	34-24-11	D03681		6		GD00179	ST..	1A		YC051-YD157
0026	20		PA		3-5	SPARE	D10853	CAP	Y		GD00179	ST..	1A		YD158, YL951-YR328
0027	22		PA		8-6	34-24-15	D10851		1		D03681	CAP	Y		YC051-YD157
0028	22		PA		8-6	34-24-15	D10851		3		D03681	CAP	Y		YC051-YD157
0029	22		PA		8-6	34-24-15	D10851		5		D03681	CAP	Y		YC051-YD157
0030	22		PA		2-3	34-24-15	D10851		7		GD00104	DC..	2		YC051-YC053
0030	22		PA		2-3	34-24-15	D10851		7		GD00104	DC..	E		YC054-YD157
0031	22		PA		5-5	34-24-15	D03681	CAP	Y		GD00179	DC..	2		YC051-YC064
0031	22		PA		5-5	34-24-15	D03681	CAP	Y		GD00179	DC..	1A		YC065-YD157

WIRE LIST

D280A108

91-21-11

Section W2200

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2205		286A2205			STBY INDICATORS (RMI, SAI, ALT/SPD) TO E1-2/E1-4 (continued)											
0038		22		PA		17-4	34-24-15	D10853		D		SP02195		S		YD158
0038		20		PA		17-4	34-24-15	D10853		D		SP02195		S		YL951-YR328
0039		20		PA		3-5	34-24-15	D10853		E		GD00179	DC..	1A		YD158, YL951-YR328
0040		20		PA		3-5	34-24-15	D10853		T-		GD00179	ST..	1A		YD158, YL951-YR328
0054		22		PA		11-7	34-22-11	D03679		54		SP02185		S		YC051-YD157
0054		22		PA		12-7	34-22-11	D03679		54		SP02185		S		YD158, YL951-YR328
0055		20		PA		3-5	34-22-11	D03679		55		GD00179	AC..	1A		YC051-YD158, YL951-YR328
0056		20		PA		3-5	34-22-11	D03679		3		GD00179	DC..	1A		YC051-YD158, YL951-YR328
2001B		24		Y2	AA	29-11	34-21-13	D03679		42		D04205J		2		YC051-YD158, YL951-YR328
2001R		24		Y2	AA	0-0	34-21-13	D03679		41		D04205J		1		YC051-YD158, YL951-YR328
2001Z					AA	0-0	34-21-13	D03679		DED		D04205J		S/R		YC051-YD158, YL951-YR328
2002B		24		Y2	AB	29-11	34-57-11	D03679		19		D04205J		4		YC051-YD158, YL951-YR328
2002R		24		Y2	AB	0-0	34-57-11	D03679		18		D04205J		3		YC051-YD158, YL951-YR328
2002Z					AB	0-0	34-57-11	D03679		DED		D04205J		S/R		YC051-YD158, YL951-YR328
2003B		24		Y2	AC	29-11	34-51-11	D03679		39		D04205J		6		YC051-YD158, YL951-YR328
2003R		24		Y2	AC	0-0	34-51-11	D03679		38		D04205J		5		YC051-YD158, YL951-YR328
2003Z					AC	0-0	34-51-11	D03679		DED		D04205J		S/R		YC051-YD158, YL951-YR328
2004B		24		Y2	AD	29-11	34-31-11	D03681		16		D04205J		11		YC051-YD157
2004B		24		Y2	AD	29-10	SPARE	D10853		CAP	Y	D04205J		11		YD158, YL951-YR328
2004R		24		Y2	AD	0-0	34-31-11	D03681		15		D04205J		10		YC051-YD157
2004R		24		Y2	AD	0-0	SPARE	D10853		CAP	Y	D04205J		10		YD158, YL951-YR328
2004Z					AD	0-0	34-31-11	D03681		S/R		D04205J		S/R		YC051-YD157
2004Z					AD	0-0	SPARE	D10853		DED		D04205J		S/R		YD158, YL951-YR328
2011B		24		Y2	AE	31-11	34-21-13	D04205J		9		D03681		CAP	Y	YC051-YD157
2011B		24		Y2	AE	29-10	34-21-13	D04205J		9		D10853		S		YD158, YL951-YR328
2011R		24		Y2	AE	0-0	34-21-13	D04205J		8		D03681		CAP	Y	YC051-YD157
2011R		24		Y2	AE	0-0	34-21-13	D04205J		8		D10853		T		YD158, YL951-YR328
2011Z					AE	0-0	34-21-13	D04205J		S/R		D03681		DED		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W2200

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2205 286A2205 STBY INDICATORS (RMI, SAI, ALT/SPD) TO E1-2/E1-4 (continued)																
2011Z					AE	0-0	34-21-13	D04205J		S/R		D10853	DED			YD158, YL951-YR328
2012B	24		Y2		AF	29-7	31-62-21	D40049J		4		D03681	CAP	Y		YC051-YD157
2012B	24		Y2		AF	27-7	SPARE	D40049J		4		D10853	CAP	Y		YD158, YL951-YR328
2012R	24		Y2		AF	0-0	31-62-21	D40049J		3		D03681	CAP	Y		YC051-YD157
2012R	24		Y2		AF	0-0	SPARE	D40049J		3		D10853	CAP	Y		YD158, YL951-YR328
2012Z					AF	0-0	31-62-21	D40049J		S/R		D03681	DED			YC051-YD157
2012Z					AF	0-0	SPARE	D40049J		S/R		D10853	DED			YD158, YL951-YR328
2013B	24		Y2		AG	31-11	31-62-11	D04205J		15		D03681	CAP	Y		YC051-YD157
2013B	24		Y2		AG	29-10	34-31-11	D04205J		15		D10853	W			YD158, YL951-YR328
2013R	24		Y2		AG	0-0	31-62-11	D04205J		14		D03681	CAP	Y		YC051-YD157
2013R	24		Y2		AG	0-0	34-31-11	D04205J		14		D10853	A			YD158, YL951-YR328
2013Z					AG	0-0	31-62-11	D04205J		S/R		D03681	DED			YC051-YD157
2013Z					AG	0-0	34-31-11	D04205J		S/R		D10853	DED			YD158, YL951-YR328
2014B	24		Y2		AH	8-6	34-24-15	D10851		10		D03681	CAP	Y		YC051-YD157
2014R	24		Y2		AH	0-0	34-24-15	D10851		9		D03681	CAP	Y		YC051-YD157
2014Z					AH	0-0	34-24-15	D10851		S/R		D03681	DED			YC051-YD157
2015B	24		Y2		AJ	29-10	SPARE	D04205J		13		D10853	CAP	Y		YD158, YL951-YR328
2015R	24		Y2		AJ	0-0	SPARE	D04205J		12		D10853	CAP	Y		YD158, YL951-YR328
2015Z					AJ	0-0	SPARE	D04205J		S/R		D10853	DED			YD158, YL951-YR328
2020B	24		Y2		AU	29-7	22-11-51	D03681		CAP	Y	D40049J	12			YD157
2020B	24		Y2		AU	27-7	22-11-51	D10853		P	VP	D40049J	12			YD158
2020B	24		Y2		AU	27-7	22-11-51	D10853		P		D40049J	12			YL951-YR328
2020R	24		Y2		AU	0-0	22-11-51	D03681		CAP	Y	D40049J	11			YD157
2020R	24		Y2		AU	0-0	22-11-51	D10853		R	VP	D40049J	11			YD158
2020R	24		Y2		AU	0-0	22-11-51	D10853		R		D40049J	11			YL951-YR328
2020Z					AU	0-0	22-11-51	D03681		DED		D40049J	S/R			YD157
2020Z					AU	0-0	22-11-51	D10853		DED		D40049J	S/R			YD158, YL951-YR328
2501B	24		Y2		BA	27-7	34-21-23	D03679		45		D40049J	2			YC051-YD158, YL951-YR328
2501R	24		Y2		BA	0-0	34-21-23	D03679		44		D40049J	1			YC051-YD158, YL951-YR328
2501Z					BA	0-0	34-21-23	D03679		DED		D40049J	S/R			YC051-YD158, YL951-YR328
2502B	24		Y2		BB	27-7	34-57-21	D03679		32		D40049J	8			YC051-YD158, YL951-YR328
2502R	24		Y2		BB	0-0	34-57-21	D03679		31		D40049J	7			YC051-YD158, YL951-YR328
2502Z					BB	0-0	34-57-21	D03679		DED		D40049J	S/R			YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W2200

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W2205	286A2205	STBY INDICATORS (RMI, SAI, ALT/SPD) TO E1-2/E1-4 (continued)													
2503B	24	Y2	BC	27-7	34-51-21	D03679	49		D40049J	10			YC051-YD158, YL951-YR328		
2503R	24	Y2	BC	0-0	34-51-21	D03679	48		D40049J	9			YC051-YD158, YL951-YR328		
2503Z			BC	0-0	34-51-21	D03679	DED		D40049J	S/R			YC051-YD158, YL951-YR328		
2504B	24	Y2	BD	27-7	SPARE	D03681	12	VP	D40049J	12			YC051-YD155		
2504R	24	Y2	BD	0-0	SPARE	D03681	11	VP	D40049J	11			YC051-YD155		
2504Z			BD	0-0	SPARE	D03681	DED		D40049J	S/R			YC051-YD155		
W2207	286A2207	PRIMARY CDS-DEU TO P1													
0003	22	PA		29-0	SPARE	D04207P	13		D04267P	A13			YC051-YC055		
0003	22	PA		29-11	SPARE	D04207P	13		D04267P	A13			YC056-YR328		
0004	22	PA		29-0	SPARE	D04207P	14		D04267P	A14			YC051-YC055		
0004	22	PA		29-11	SPARE	D04207P	14		D04267P	A14			YC056-YR328		
0013	22	PA		22-8	34-41-11	D40081P	A09		D04267P	B13			YC051-YC052		
0014	22	PA		22-8	34-41-11	D40081P	A08		D04267P	B14			YC051-YC052		
0031	22	PA		29-0	SPARE	D04207P	31		D04267P	B11			YC051-YC055		
0031	22	PA		29-11	SPARE	D04207P	31		D04267P	B11			YC056-YR328		
0032	22	PA		29-0	SPARE	D04207P	32		D04267P	B12			YC051-YC055		
0032	22	PA		29-11	SPARE	D04207P	32		D04267P	B12			YC056-YR328		
0033	22	PA		15-8	34-41-11	D04207P	33		D40081P	A10			YC051-YC052		
0036	22	PA		22-8	34-41-11	D40081P	A03		D04267P	B16			YC051-YC052		
0037	22	PA		29-0	SPARE	D04207P	37		D04267P	B17			YC051-YC055		
0037	22	PA		29-11	SPARE	D04207P	37		D04267P	B17			YC056-YR328		
0038	22	PA		29-0	SPARE	D04207P	38		D04267P	B18			YC051-YC055		
0038	22	PA		29-11	SPARE	D04207P	38		D04267P	B18			YC056-YR328		
0040	22	CQ		29-0	SPARE	D04207P	40		D04267P	B19			YC051-YC055		
0040	22	CQ		29-11	SPARE	D04207P	40		D04267P	B19			YC056-YR328		
0041	22	CQ		29-0	SPARE	D04207P	41		D04267P	B20			YC051-YC055		
0041	22	CQ		29-11	SPARE	D04207P	41		D04267P	B20			YC056-YR328		
2001B	24	Y2	AA	29-0	31-62-12	D04207P	2		D04267P	A02			YC051-YC055		
2001B	24	Y2	AA	29-11	31-62-12	D04207P	2		D04267P	A02			YC056-YR328		
2001R	24	Y2	AA	0-0	31-62-12	D04207P	1		D04267P	A01			ALL		
2001Z			AA	0-0	31-62-12	D04207P	S/R		D04267P	PERG	1F		ALL		
2002B	24	Y2	AB	29-0	31-62-12	D04207P	4		D04267P	A04			YC051-YC055		
2002B	24	Y2	AB	29-11	31-62-12	D04207P	4		D04267P	A04			YC056-YR328		
2002R	24	Y2	AB	0-0	31-62-12	D04207P	3		D04267P	A03			ALL		
2002Z			AB	0-0	31-62-12	D04207P	S/R		D04267P	PERG	1F		ALL		

WIRE LIST

D280A108

91-21-11

Section W2200

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2207	286A2207			PRIMARY CDS-DEU TO P1 (continued)											
2003B	24		Y2	AC	29-0	SPARE	D04207P		6		D04267P	A06			YC051-YC055
2003B	24		Y2	AC	29-11	SPARE	D04207P		6		D04267P	A06			YC056-YR328
2003R	24		Y2	AC	0-0	SPARE	D04207P		5		D04267P	A05			ALL
2003Z				AC	0-0	SPARE	D04207P		S/R		D04267P	PERG	1F		ALL
2004B	24		Y2	AD	29-0	SPARE	D04207P		8		D04267P	A08			YC051-YC055
2004B	24		Y2	AD	29-11	SPARE	D04207P		8		D04267P	A08			YC056-YR328
2004R	24		Y2	AD	0-0	SPARE	D04207P		7		D04267P	A07			ALL
2004Z				AD	0-0	SPARE	D04207P		S/R		D04267P	PERG	1F		ALL
2005B	24		Y2	AE	29-0	31-62-13	D04207P		10		D04267P	A10			YC051-YC055
2005B	24		Y2	AE	29-11	31-62-13	D04207P		10		D04267P	A10			YC056-YR328
2005R	24		Y2	AE	0-0	31-62-13	D04207P		9		D04267P	A09			ALL
2005Z				AE	0-0	31-62-13	D04207P		S/R		D04267P	PERG	1F		ALL
2006B	24		Y2	AF	15-8	31-62-13	D04207P		12		D40081P	A02			YC051-YC052
2006R	24		Y2	AF	0-0	31-62-13	D04207P		11		D40081P	A01			YC051-YC052
2006Z				AF	0-0	31-62-13	D04207P		S/R		D40081P	PERG	1F		YC051-YC052
2007B	24		7K	AG	22-8	34-41-11	D04267P		A12		D40081P	A05			YC051-YC052
2007W	24		7K	AG	0-0	34-41-11	D04267P		A11		D40081P	A04			YC051-YC052
2007Z				AG	0-0	34-41-11	D04267P	PERG	1F		D40081P	PERG	1F		YC051-YC052
2008B	24		Y2	AH	29-0	SPARE	D04207P		16		D04267P	A16			YC051-YC055
2008B	24		Y2	AH	29-11	SPARE	D04207P		16		D04267P	A16			YC056-YR328
2008R	24		Y2	AH	0-0	SPARE	D04207P		15		D04267P	A15			ALL
2008Z				AH	0-0	SPARE	D04207P		S/R		D04267P	PERG	1F		ALL
2009B	22		X2	AJ	29-0	22-23-12	D04207P		18		D04267P	A18			YC051-YC055
2009B	22		X2	AJ	29-11	22-23-12	D04207P		18		D04267P	A18			YC056-YL959
2009B	22		X2	AJ	29-11	SPARE	D04207P		18		D04267P	A18			YL963-YN235
2009B	22		X2	AJ	29-11	MULTI	D04207P		18		D04267P	A18			YN236-YR328
2009R	22		X2	AJ	0-0	22-23-12	D04207P		17		D04267P	A17			YC051-YL959
2009R	22		X2	AJ	0-0	SPARE	D04207P		17		D04267P	A17			YL963-YN235
2009R	22		X2	AJ	0-0	MULTI	D04207P		17		D04267P	A17			YN236-YR328
2009Z				AJ	0-0	22-23-12	D04207P		S/R		D04267P	PERG	1F		YC051-YL959
2009Z				AJ	0-0	SPARE	D04207P		S/R		D04267P	PERG	1F		YL963-YN235
2009Z				AJ	0-0	MULTI	D04207P		S/R		D04267P	PERG	1F		YN236-YR328
2010B	24		Y2	AK	29-0	SPARE	D04207P		20		D04267P	A20			YC051-YC055
2010B	24		Y2	AK	29-11	SPARE	D04207P		20		D04267P	A20			YC056-YR328
2010R	24		Y2	AK	0-0	SPARE	D04207P		19		D04267P	A19			ALL
2010Z				AK	0-0	SPARE	D04207P		S/R		D04267P	PERG	1F		ALL
2011B	22		X2	AL	23-1	28-41-11	TB1806X	A008	1A		D04267P	B02			YC051-YC055
2011B	22		X2	AL	24-1	28-41-11	TB1806X	A008	1A		D04267P	B02			YC056-YR328
2011R	22		X2	AL	0-0	28-41-11	TB1806X	A007	1A		D04267P	B01			ALL

WIRE LIST

D280A108

91-21-11

Section W2200

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description		From				To						
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W2207		286A2207			PRIMARY CDS-DEU TO P1 (continued)												
2011Z					AL	0-0	28-41-11	GB01806	ST..	1A		D04267P	PERG	1F		ALL	
2012B		22	X2		AM	23-1	28-41-11	TB1806X	A006	1A		D04267P	B04			YC051-YC055	
2012B		22	X2		AM	24-1	28-41-11	TB1806X	A006	1A		D04267P	B04			YC056-YR328	
2012R		22	X2		AM	0-0	28-41-11	TB1806X	A005	1A		D04267P	B03			ALL	
2012Z					AM	0-0	28-41-11	GB01806	ST..	1A		D04267P	PERG	1F		ALL	
2013B		24	Y2		AN	22-8	34-41-11	D40081P	A07			D04267P	B06			YC051-YC052	
2013R		24	Y2		AN	0-0	34-41-11	D40081P	A06			D04267P	B05			YC051-YC052	
2013Z					AN	0-0	34-41-11	D40081P	PERG	1F		D04267P	PERG	1F		YC051-YC052	
2017B		24	Y2		AI	29-0	34-58-11	D04207P		22		D04267P	B08			YC053-YC055	
2017B		24	Y2		AI	29-11	34-58-11	D04207P		22		D04267P	B08			YC056-YR328	
2017R		24	Y2		AI	0-0	34-58-11	D04207P		21		D04267P	B07			YC053-YR328	
2017Z					AI	0-0	34-58-11	D04207P		S/R		D04267P	PERG	1F		YC053-YR328	
W2208		286A2208			WINDSHIELD HEAT DISCONNECT TO E4-2. (RB1)												
1001		18	X1		AA	3-4	30-41-12	A00010		3	E	*	A00010	4	E	YC051-YD158, YL951-YR328	
1001Z					AA	0-0	30-41-12	A00010		DED			A00010	DED		YC051-YD158, YL951-YR328	
1002		18	X1		AB	29-5	30-41-12	A00010		3	E	*	D40068P	F		YC051-YC055	
1002		18	X1		AB	31-0	30-41-12	A00010		3	E	*	D40068P	F		YC056-YD158, YL951-YN236, YN501-YR319	
1002		18	X1		AB	30-8	30-41-12	A00010		3	E	*	D40068P	F		YN237-YN260, YR320-YR328	
1002Z					AB	0-0	30-41-12	A00010				AC	D40068P	PERG	1F	YC051-YD158, YL951-YR328	
1003		18	X1		AC	2-7	30-41-12	D10568		3	18		GD01354	AC..	E	*	YC051-YD158, YL951-YR328
1003Z					AC	0-0	30-41-12	D10568				AB	GD01354	AC..	E	*	YC051-YD158, YL951-YR328
1004		20	X1		AD	35-7	30-41-12	D10568		4			D40068P	A03		YC051-YC052	
1004		20	X1		AD	35-4	30-41-12	D10568		4			D40068P	A03		YC053-YC055	
1004		20	X1		AD	36-10	30-41-12	D10568		4			D40068P	A03		YC056-YD158, YL951-YL956, YN231-YN235	
1004		20	X1		AD	37-3	30-41-12	D10568		4			D40068P	A03		YL957-YL999, YN236, YN501-YR319	
1004		20	X1		AD	37-0	30-41-12	D10568		4			D40068P	A03		YN237-YN260, YR320-YR328	

WIRE LIST

D280A108

91-21-11

Section W2200

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY	Description Fam	Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W2208	286A2208	WINDSHIELD HEAT DISCONNECT TO E4-2. (RB1) (continued)										
1004Z		AD	0-0	30-41-12	D10568		AB	D40068P	PERG	1F		YC051-YD158, YL951-YR328
2001B	20	X2 GA	35-7	30-41-12	D10568	2		D40068P	A08			YC051-YC052
2001B	20	X2 GA	35-4	30-41-12	D10568	2		D40068P	A08			YC053-YC055
2001B	20	X2 GA	36-10	30-41-12	D10568	2		D40068P	A08			YC056-YD158, YL951-YL956, YN231-YN235
2001B	20	X2 GA	37-3	30-41-12	D10568	2		D40068P	A08			YL957-YL999, YN236, YN501-YR319
2001B	20	X2 GA	37-0	30-41-12	D10568	2		D40068P	A08			YN237-YN260, YR320-YR328
2001R	20	X2 GA	0-0	30-41-12	D10568	1		D40068P	A07			YC051-YD158, YL951-YR328
2001Z		GA	0-0	30-41-12	D10568		AB	D40068P	PERG	1F		YC051-YD158, YL951-YR328
2002B	20	X2 GB	25-6	30-41-12	A00010	=D	C	S01079	4	C		YC051-YC055
2002B	20	X2 GB	25-9	30-41-12	A00010	=D	C	S01079	4	C		YC056-YD158, YL951-YN236, YN501-YR319
2002B	20	X2 GB	25-8	30-41-12	A00010	=D	C	S01079	4	C		YN237-YN260, YR320-YR328
2002R	20	X2 GB	0-0	30-41-12	A00010	=C	C	S01079	1	C		YC051-YD158, YL951-YR328
2002Z		GB	0-0	30-41-12	A00010		AC	S01079			AD	YC051-YD158, YL951-YR328
2003B	20	X2 GC	25-9	30-41-12	A00010	=A	C	S01079	6	C		YC051-YC055
2003B	20	X2 GC	26-0	30-41-12	A00010	=A	C	S01079	6	C		YC056-YD158, YL951-YN236, YN501-YR319
2003B	20	X2 GC	25-11	30-41-12	A00010	=A	C	S01079	6	C		YN237-YN260, YR320-YR328
2003R	20	X2 GC	0-0	30-41-12	A00010	=B	C	S01079	3	C		YC051-YD158, YL951-YR328
2003Z		GC	0-0	30-41-12	A00010		AC	S01079			AD	YC051-YD158, YL951-YR328
2004B	20	X2 GD	8-8	30-41-12	S01079	5	C	D40068P	A06			YC051-YC055
2004B	20	X2 GD	10-4	30-41-12	S01079	5	C	D40068P	A06			YC056-YD158, YL951-YN236, YN501-YR319

WIRE LIST
D280A108

91-21-11
Section W2200
Page 10
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To															
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity						
W2208	286A2208	WINDSHIELD HEAT DISCONNECT TO E4-2. (RB1) (continued)																	
2004B	20 X2	GD	10-1	30-41-12	S01079	5	C		D40068P	A06								YN237-YN260, YR320-YR328	
2004R	20 X2	GD	0-0	30-41-12	S01079	2	C		D40068P	A05								YC051-YD158, YL951-YR328	
2004Z		GD	0-0	30-41-12	S01079	DED			D40068P	PERG	1F							YC051-YD158, YL951-YR328	
5501	18 PA		2-0	30-42-11	GD00104	DC..	E		D00064	1								YC051-YC063	
5501	16 PA		2-0	30-42-11	GD00104	DC..	E		D00064	1								YC064-YD158, YL951-YR328	
5502	18 GA		22-0	30-42-11	TB0606V	A013	1		D00064	2								YC051-YC055	
5502	18 PA		22-0	30-42-11	TB0606V	A013	1		D00064	2								YC056-YC061	
5502	18 PA		14-4	30-42-11	SP01082		9		D00064	2								YC062-YC063	
5502	14 PA		1-0	30-42-11	SM00001		9		D00064	2	14							YC064-YD158, YL951-YR328	
5503	24 PK		22-1	30-42-11	TB0608X	A001	1A		D00064	3								YC051-YD158, YL951-YN236, YN501-YR319	
5503	24 PK		22-6	30-42-11	TB0608X	A001	1A		D00064	3								YN237-YN260, YR320-YR328	
5504	10 PA		13-10	30-42-11	SP01082		9		SM00001		9							YC064-YD158, YL951-YR328	
FRAB			0-0	30-41-12	D10568	5			D10568								AB	YC051-YD158, YL951-YR328	
FRAC			0-0	30-41-12	A00010			AC	GD00980	ST..	E							YC051-YD158, YL951-YR328	
FRAD			0-0	30-41-12	S01079			AD	GD00568	ST..	E							YC051-YD158, YL951-YR328	

WIRE LIST

D280A108

91-21-11

Section W2200

Page 11 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I	W2212	286A2212				P5 OVHD PANEL (RA1)									
	0001	20	CQ		7-8	33-42-11	S00259		2	C	D40524P		1		YC051-YC052
I	0001	20	CQ		8-3	33-42-11	S00259		2	C	D40524P		1		YC053-YR328
	0002	18	CQ		7-1	33-42-11	S00259		1	C	D40528P		21		YC051-YC052
I	0002	18	CQ		7-3	33-42-11	S00259		1	C	D40528P		21		YC053-YR328
	0005	18	PA		7-10	33-45-11	S00269		3	C	D40524P		4		YC051-YC052
I	0005	18	PA		8-6	33-45-11	S00269		3	C	D40524P		4		YC053-YR328
	0006	16	PA		7-3	33-45-11	S00269		1	C	D40528P		23		YC051-YC052
I	0006	16	PA		7-6	33-45-11	S00269		1	C	D40528P		23		YC053-YR328
I	0501	20	PA		6-7	27-23-11	D00624		22		D40526P		11		ALL
	0502	22	PA		5-4	27-23-11	D00624		40		TB0261X	A004	1A		YC051-YC052
	0502	22	PA		5-3	27-23-11	D00624		40		TB0261X	A004	1A		YC053-YC058
	0502	22	PA		5-2	27-23-11	D00624		40		TB0261X	A004	1A		YC059-YC064
I	0502	22	PA		6-5	27-23-11	D00624		40		TB0261X	A004	1A		YC065-YR328
	0503	20	PA		4-11	27-23-11	D00624		12		D40528P		3		YC051-YC052
	0503	20	PA		5-3	27-23-11	D00624		12		D40528P		3		YC053-YC058
I	0503	20	PA		5-2	27-23-11	D00624		12		D40528P		3		YC059-YR328
	0504	20	PA		4-11	27-23-11	D00624		3		D40528P		4		YC051-YC052
	0504	20	PA		5-3	27-23-11	D00624		3		D40528P		4		YC053-YC058
I	0504	20	PA		5-2	27-23-11	D00624		3		D40528P		4		YC059-YR328
	0505	22	PA		5-1	27-23-11	D00630		40		D40528P		5		YC051-YC052
	0505	22	PA		5-4	27-23-11	D00630		40		D40528P		5		YC053-YC058
I	0505	22	PA		5-3	27-23-11	D00630		40		D40528P		5		YC059-YR328
	0508	20	PA		6-9	27-61-11	D00630		24		D40526P		12		YC051-YC052
	0508	20	PA		6-8	27-61-11	D00630		24		D40526P		12		YC053-YC058
I	0508	20	PA		6-7	27-61-11	D00630		24		D40526P		12		YC059-YR328
	0511	22	CQ		5-5	27-23-14	D00624		18		TB0262X	B003	1A		YC051-YC052
	0511	22	CQ		5-4	27-23-14	D00624		18		TB0262X	B003	1A		YC053-YC064
I	0511	22	CQ		6-4	27-23-14	D00624		18		TB0262X	B003	1A		YC065-YR328
	0512	20	CQ		2-7	27-23-14	D00624		7		GD00507	DC..	1A		YC051-YC052
I	0512	20	CQ		2-4	27-23-14	D00624		7		GD00517	DC..	1A		YC053-YR328
	0513	22	PA		7-0	29-11-11	D00642		9		D40526P		13		YC051-YC052, YC059-YC064
I	0513	22	PA		6-11	29-11-11	D00642		9		D40526P		13		YC053-YC058, YC065-YR328
	0514	22	PA		5-4	29-11-11	D00642		10		D40528P		14		YC051-YC052
I	0514	22	PA		6-1	29-11-11	D00642		10		D40528P		14		YC053-YR328
	0515	22	CQ		20-1	29-11-12	D00642		14		D46124P	A01			YC051-YC052
I	0515	22	CQ		19-7	29-11-12	D00642		14		D46124P	A01			YC053-YC058, YC065-YR328

WIRE LIST

D280A108

91-21-11

Section W2210

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2212	286A2212			P5 OVHD PANEL (RA1) (continued)											
0515	22		CQ		19-8	29-11-12	D00642		14		D46124P	A01			YC059-YC064
0516	22		CQ		20-1	29-11-12	D00642		13		D46124P	A02			YC051-YC052
0516	22		CQ		19-7	29-11-12	D00642		13		D46124P	A02			YC053-YC058, YC065-YR328
0516	22		CQ		19-8	29-11-12	D00642		13		D46124P	A02			YC059-YC064
0517	20		PA		5-1	27-23-11	D00630		9		D40528P	17			YC051-YC052
0517	20		PA		5-4	27-23-11	D00630		9		D40528P	17			YC053-YC058
0517	20		PA		5-3	27-23-11	D00630		9		D40528P	17			YC059-YR328
0518	20		PA		5-1	27-23-11	D00630		21		D40528P	18			YC051-YC052
0518	20		PA		5-4	27-23-11	D00630		21		D40528P	18			YC053-YC058
0518	20		PA		5-3	27-23-11	D00630		21		D40528P	18			YC059-YR328
0519	20		CQ		6-7	27-23-11	D00624		11		D40526P	5			ALL
0520	20		CQ		5-5	27-23-11	D00624		25		TB0262X	A002	1A		YC051-YC052
0520	20		CQ		5-4	27-23-11	D00624		25		TB0262X	A002	1A		YC053-YC064
0520	20		CQ		6-4	27-23-11	D00624		25		TB0262X	A002	1A		YC065-YR328
0521	20		CQ		6-1	27-23-11	D00630		22		TB0262X	A003	1A		YC051-YC052
0521	20		CQ		5-5	27-23-11	D00630		22		TB0262X	A003	1A		YC053-YC058
0521	20		CQ		5-4	27-23-11	D00630		22		TB0262X	A003	1A		YC059-YC064
0521	20		CQ		6-5	27-23-11	D00630		22		TB0262X	A003	1A		YC065-YR328
0522	22		CQ		19-8	29-22-11	D00624		21		D46124P	A03			YC051-YC052
0522	22		CQ		19-3	29-22-11	D00624		21		D46124P	A03			YC053-YR328
0523	20		GA		8-0	29-35-11	D00630		37		GD00510	DC..	1		YC051-YC052
0523	20		GA		8-0	29-35-11	D00630		37		GD00520	DC..	1A		YC053-YD155
0523	20		PA		5-0	29-35-11	D00630		37		GD00520	DC..	1A		YD157-YR328
0524	24		GK		8-0	29-35-11	D00630		52		D00630	53			YC051-YD155
0524	24		PK		0-7	29-35-11	D00630		52		D00630	53			YD157-YR328
0525	24		GK		8-0	29-35-11	D00624		52		D00624	53			YC051-YD155
0525	24		PK		0-7	29-35-11	D00624		52		D00624	53			YD157-YR328
0526	20		GA		8-0	29-35-11	D00624		37		GD00510	DC..	1		YC051-YC052
0526	20		GA		8-0	29-35-11	D00624		37		GD00520	DC..	1A		YC053-YD155
0526	20		PA		4-11	29-35-11	D00624		37		GD00520	DC..	1A		YD157-YR328
5505	18		CQ		3-10	30-42-11	TB0503V	B031	1		D40524P	10			YC051-YC052
5505	18		CQ		4-4	30-42-11	TB0503V	B031	1		D40524P	10			YC053-YC058
5505	18		CQ		4-3	30-42-11	TB0503V	B031	1		D40524P	10			YC059-YC064
5505	18		CQ		4-6	30-42-11	TB0503V	B031	1		D40524P	10			YC065-YR328
5551	22		PA		6-3	30-31-12	D40524P		2		D00638	22			YL968-YL999, YN236-YR328
5552	22		PA		6-3	30-31-12	D40524P		3		D00638	24			YL968-YL999, YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W2210

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2212	286A2212				P5 OVHD PANEL (RA1) (continued)										
5553	22		PA		6-3	30-31-12	D40524P	5			D00638	23			YL968-YL999, YN236-YR328
5554	22		PA		6-3	30-31-12	D40524P	6			D00638	25			YL968-YL999, YN236-YR328
5555	22		PA		4-10	30-31-12	D40524P	8			SP00875		9		YL968-YL999, YN236-YR328
W2214	286A2214				P5 OVHD PANEL TO EE BAY (E4-1) RB1										
0002	20		PA		0-7	33-42-11	S00260	5	C		S00260	2	C		YC051-YD158, YL951-YR328
0003	20		PA		32-1	33-42-11	S00260	3	C		D40530P	A01			YC051-YC052
0003	20		PA		31-2	33-42-11	S00260	3	C		D40530P	A01			YC053-YC055
0003	20		PA		31-5	33-42-11	S00260	3	C		D40530P	A01			YC056-YC058
0003	20		PA		31-9	33-42-11	S00260	3	C		D40530P	A01			YC059-YD158, YL951-YR328
0004	20		PA		32-1	33-42-11	S00260	4	C		D40530P	B01			YC051-YC052
0004	20		PA		31-2	33-42-11	S00260	4	C		D40530P	B01			YC053-YC055
0004	20		PA		31-5	33-42-11	S00260	4	C		D40530P	B01			YC056-YC058
0004	20		PA		31-9	33-42-11	S00260	4	C		D40530P	B01			YC059-YD158, YL951-YR328
0005	20		PA		32-1	33-42-11	S00260	6	C		D40530P	A02			YC051-YC052
0005	20		PA		31-2	33-42-11	S00260	6	C		D40530P	A02			YC053-YC055
0005	20		PA		31-5	33-42-11	S00260	6	C		D40530P	A02			YC056-YC058
0005	20		PA		31-9	33-42-11	S00260	6	C		D40530P	A02			YC059-YD158, YL951-YR328
0506	24		PK		30-10	29-33-11	D02486	5			D40530P	A10			YC051-YC052
0506	24		PK		30-1	29-33-11	D02486	5			D40530P	A10			YC053-YC055
0506	24		PK		30-7	29-33-11	D02486	5			D40530P	A10			YC056-YC058
0506	24		PK		30-8	29-33-11	D02486	5			D40530P	A10			YC059-YD158, YL951-YR328
5501	18		PA		7-6	30-42-11	S00022	22	C		TB0503V	B031	1		YC051-YC052
5501	18		PA		7-2	30-42-11	S00022	22	C		TB0503V	B031	1		YC053-YC055
5501	18		PA		6-11	30-42-11	S00022	22	C		TB0503V	B031	1		YC056-YC058
5501	18		PA		7-4	30-42-11	S00022	22	C		TB0503V	B031	1		YC059-YC064
5501	18		PA		7-9	30-42-11	S00022	22	C		TB0503V	B031	1		YC065-YD158, YL951-YR328
5502	18		PA		19-5	SPARE	TB0503V	B031	1		TB0606V	A013	1		YC051-YC052
5502	18		PA		18-5	SPARE	TB0503V	B031	1		TB0606V	A013	1		YC053-YC058
5502	18		PA		18-5	00-000	TB0503V	B031	1		TB0606V	A013	1		YC059-YC064

WIRE LIST

D280A108

91-21-11

Section W2210

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W2214	286A2214	P5 OVHD PANEL TO EE BAY (E4-1) RB1 (continued)													
5502	18 PA		18-8	00-000	TB0503V	B031	1		TB0606V	A013	1			YC065-YD158	
5502	18 PA		18-8	SPARE	TB0503V	B031	%A		TB0606V	A013	1			YL951-YL999, YR301-YR328	
5502	18 PA		18-8	00-000	TB0503V	B031	%A		TB0606V	A013	1			YN231-YN501	
W2216	286A2216	P5 OVHD PANEL TO EE BAY (E4-1) RA2													
0002	24 PK		20-3	52-71-11	D46112P		7		SM00001		S			YC051-YC052	
0002	24 PK		19-7	52-71-11	D46112P		7		SM00001		S			YC053-YC058	
0002	24 PK		19-9	52-71-11	D46112P		7		SM00001		S			YC059-YD151	
0002	24 PK		19-9	52-71-11	SM00001		S		D46112P	7				YD152-YD158	
0002	24 PK		19-9	52-71-11	D01406		8		SM00001		S			YD160-YR323, YR325-YR328	
0003	24 PK		20-3	52-71-11	D01406		5		D46112P	10				YC051-YC052	
0003	24 PK		19-7	52-71-11	D01406		5		D46112P	10				YC053-YC058	
0003	24 PK		19-9	52-71-11	D01406		5		D46112P	10				YC059-YR323, YR325-YR328	
0004	24 PK		20-3	52-71-11	D01406		2		D46112P	8				YC051-YC052	
0004	24 PK		19-7	52-71-11	D01406		2		D46112P	8				YC053-YC058	
0004	24 PK		19-9	52-71-11	D01406		2		D46112P	8				YC059-YR323, YR325-YR328	
0005	24 PK		20-3	52-71-11	D01406		3		D46112P	11				YC051-YC052	
0005	24 PK		19-7	52-71-11	D01406		3		D46112P	11				YC053-YC058	
0005	24 PK		19-9	52-71-11	D01406		3		D46112P	11				YC059-YR323, YR325-YR328	
0006	24 PK		20-3	52-71-12	D01406		1		D46112P	12				YC051-YC052	
0006	24 PK		19-7	52-71-12	D01406		1		D46112P	12				YC053-YC058	
0006	24 PK		19-9	52-71-12	D01406		1		D46112P	12				YC059-YR323, YR325-YR328	
0008	24 PK		20-3	52-71-12	D01406		6		D46112P	13				YC051-YC052	
0008	24 PK		19-7	52-71-12	D01406		6		D46112P	13				YC053-YC058	
0008	24 PK		19-9	52-71-12	D01406		6		D46112P	13				YC059-YR323, YR325-YR328	
0012	24 PK		0-10	52-71-11	D01406		8		SM00001		S			YC051-YD151	
0012	24 PK		10-0	52-71-11	D01406		8		SM00001		S			YD152-YD158	
0012	24 PK		0-7	52-71-11	D46112P		7		SM00001		S			YD160-YR323, YR325-YR328	
0014	24 PK		16-10	52-71-11	SM00001		S		TB0506X	A016	1A			YD160-YR323, YR325-YR328	
0015	24 PK		50-0	52-71-11	SP00533		9		SM00001		S			YC051-YD158	

WIRE LIST

D280A108

91-21-11

Section W2210

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity			
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice	
W2216	286A2216			P5 OVHD PANEL TO EE BAY (E4-1) RA2 (continued)												
1301	24	Y1	EN		20-2	73-21-12	D03172		10			TB0606Y	B005	1A		YC051-YC052
1301	24	Y1	EN		19-10	73-21-12	D03172		10			TB0606Y	B005	1A		YC053-YC058
1301	24	Y1	EN		19-8	73-21-12	D03172		10			TB0606Y	B005	1A		YC059-YR323, YR325-YR328
1301Z			EN		0-0	73-21-12	D03172				AA	GB00606	ST..	1A		YC051-YR323, YR325-YR328
2001B	24	PL	GA		33-6	21-61-11	D41812P		A07			D10958	2			YC051-YC052
2001B	24	PL	GA		32-10	21-61-11	D41812P		A07			D10958	2			YC053-YL999, YR301-YR323, YR325-YR328
2001R	24	PL	GA		0-0	21-61-11	D41812P		A06			D10958	1			YC051-YL999, YR301-YR323, YR325-YR328
2002B	24	PL	GB		33-6	21-61-12	D41812P		B07			D10958	4			YC051-YC052
2002B	24	PL	GB		32-10	21-61-12	D41812P		B07			D10958	4			YC053-YL999, YR301-YR323, YR325-YR328
2002R	24	PL	GB		0-0	21-61-12	D41812P		B06			D10958	3			YC051-YL999, YR301-YR323, YR325-YR328
2601B	24	Y2	SA		4-4	73-21-12	D03172		13			TB0262X	B001	1A		YC051-YC058
2601B	24	Y2	SA		4-2	73-21-12	D03172		13			TB0262X	B001	1A		YC059-YC064
2601B	24	Y2	SA		4-8	73-21-12	D03172		13			TB0262X	B001	1A		YC065-YR323, YR325-YR328
2601R	24	Y2	SA		0-0	73-21-12	D03172		24			TB0262X	A001	1A		YC051-YR323, YR325-YR328
2601Z			SA		0-0	73-21-12	D03172				AA	GB00261	ST..	1A		YC051-YR323, YR325-YR328
3001B	24	PM	WA		35-8	21-61-11	D41812P		A10			D03996	11			YC051-YC052
3001B	24	PM	WA		35-1	21-61-11	D41812P		A10			D03996	11			YC053-YL999, YR301-YR323, YR325-YR328
3001R	24	PM	WA		0-0	21-61-11	D41812P		A09			D03996	10			YC051-YL999, YR301-YR323, YR325-YR328
3001Y	24	PM	WA		0-0	21-61-11	D41812P		A08			D03996	9			YC051-YL999, YR301-YR323, YR325-YR328
3002B	24	PM	WB		35-8	21-61-12	D41812P		B05			D03996	6			YC051-YC052

WIRE LIST
D280A108

91-21-11
Section W2210
Page 5
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2216	286A2216				P5 OVHD PANEL TO EE BAY (E4-1) RA2 (continued)										
3002B	24		PM	WB	35-1	21-61-12	D41812P	B05			D03996	6			YC053-YL999, YR301-YR323, YR325-YR328
3002R	24		PM	WB	0-0	21-61-12	D41812P	B04			D03996	5			YC051-YL999, YR301-YR323, YR325-YR328
3002Y	24		PM	WB	0-0	21-61-12	D41812P	B03			D03996	4			YC051-YL999, YR301-YR323, YR325-YR328
3003B	24		PM	WC	35-8	21-61-14	D41812P	A12			D03996	14			YC051-YC052
3003B	24		PM	WC	35-1	21-61-14	D41812P	A12			D03996	14			YC053-YL999, YR301-YR323, YR325-YR328
3003R	24		PM	WC	0-0	21-61-14	D41812P	A13			D03996	15			YC051-YL999, YR301-YR323, YR325-YR328
3003Y	24		PM	WC	0-0	21-61-14	D41812P	A14			D03996	16			YC051-YL999, YR301-YR323, YR325-YR328
3004B	24		PM	WD	35-8	21-61-14	D41812P	A16			D03996	21			YC051-YC052
3004B	24		PM	WD	35-1	21-61-14	D41812P	A16			D03996	21			YC053-YL999, YR301-YR323, YR325-YR328
3004R	24		PM	WD	0-0	21-61-14	D41812P	A17			D03996	22			YC051-YL999, YR301-YR323, YR325-YR328
3004Y	24		PM	WD	0-0	21-61-14	D41812P	A18			D03996	23			YC051-YL999, YR301-YR323, YR325-YR328
5501	22		CQ		6-0	21-27-31	L01141	2	B		TB0505Y	B011	1A		YC051-YC052
5501	22		CQ		5-5	21-27-31	L01141	2	B		TB0505Y	B011	1A		YC053-YC058
5501	22		CQ		6-1	21-27-31	L01141	2	B		TB0505Y	B011	1A		YC059-YC064
5501	22		CQ		6-5	21-27-31	L01141	2	B		TB0505Y	B011	1A		YC065-YR323, YR325-YR328
5502	22		CQ		17-6	21-27-31	TB0505Y	B011	1A		D46112P	2			YC051-YC052
5502	22		CQ		16-11	21-27-31	TB0505Y	B011	1A		D46112P	2			YC053-YC058
5502	22		CQ		16-10	21-27-31	TB0505Y	B011	1A		D46112P	2			YC059-YC064
5502	22		CQ		17-0	21-27-31	TB0505Y	B011	1A		D46112P	2			YC065-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W2210

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2216	286A2216				P5 OVHD PANEL TO EE BAY (E4-1) RA2 (continued)										
5503	24		PK		4-4	21-61-11	TB0504Y	A007	1A		D03996	7			YC051-YC052, YC059-YC064
5503	24		PK		4-1	21-61-11	TB0504Y	A007	1A		D03996	7			YC053-YC058
5503	24		PK		4-7	21-61-11	TB0504Y	A007	1A		D03996	7			YC065-YL999, YR301-YR323, YR325-YR328
5503	24		B6		3-11	21-61-21	TB0504Y	A007	1A		D40532P	13			YN231-YN501
5504	24		B6		6-6	21-61-21	D00646		16		D40532P	14			YN231-YN501
5505	24		PK		4-8	21-61-11	D00646		47		TB0504Y	A007	1A		YC051-YC052
5505	24		PK		4-4	21-61-11	D00646		47		TB0504Y	A007	1A		YC053-YC058
5505	24		PK		4-5	21-61-11	D00646		47		TB0504Y	A007	1A		YC059-YC064
5505	24		PK		4-9	21-61-11	D00646		47		TB0504Y	A007	1A		YC065-YL999, YR301-YR323, YR325-YR328
5505	24		B6		4-9	21-61-21	D00646		15		TB0504Y	A007	1A		YN231-YN501
5506	24		PK		36-0	21-61-11	D41812P		A05		D00646	40			YC051-YC052
5506	24		PK		35-4	21-61-11	D41812P		A05		D00646	40			YC053-YC058
5506	24		PK		35-3	21-61-11	D41812P		A05		D00646	40			YC059-YL999, YR301-YR323, YR325-YR328
5506	24		B6		1-7	21-61-21	D00646		25		D00618	10			YN231-YN501
5507	24		PK		3-11	21-61-11	D40532P		20		TB0504Y	A005	1A		YC051-YC052, YC065-YL999, YR301-YR323, YR325-YR328
5507	24		PK		3-10	21-61-11	D40532P		20		TB0504Y	A005	1A		YC053-YC058
5507	24		PK		3-9	21-61-11	D40532P		20		TB0504Y	A005	1A		YC059-YC064
5507	24		B6		4-9	21-61-21	D00646		26		TB0504Y	A005	1A		YN231-YN501
5508	24		PK		33-7	21-61-11	D41812P		B01		TB0504Y	A005	1A		YC051-YC052
5508	24		PK		33-1	21-61-11	D41812P		B01		TB0504Y	A005	1A		YC053-YC058, YC065-YL999, YR301-YR323, YR325-YR328
5508	24		PK		32-11	21-61-11	D41812P		B01		TB0504Y	A005	1A		YC059-YC064
5508	24		B6		4-6	21-61-21	D00618		6		TB0504Y	A005	1A		YN231-YN501
5509	24		PK		33-6	21-61-11	D40534P		A15		TB0504Y	A007	1A		YC051-YC052
5509	24		PK		33-0	21-61-11	D40534P		A15		TB0504Y	A007	1A		YC053-YC058
5509	24		PK		32-11	21-61-11	D40534P		A15		TB0504Y	A007	1A		YC059-YC064

WIRE LIST

D280A108

91-21-11
Section W2210
Page 7
Nov 12/2012

Bundle No.	Part Number			Fam	Description		Diagram	From			To				Effectivity
Wire No.	GA	CO TY	FT-IN			Equip		Term	Type	Splice	Equip	Term	Type	Splice	
W2216	286A2216			P5 OVHD PANEL TO EE BAY (E4-1) RA2 (continued)											
5509	24	PK		33-1	21-61-11	D40534P		A15			TB0504Y	A007	1A	YC065-YL999, YR301-YR323, YR325-YR328	
5509	24	B6		33-1	21-61-21	TB0504Y		A007	1A		D40534P	A15		YN231-YN501	
5510	24	PK		35-6	21-61-51	D03998		24			D40534P	B18		YC051-YC052	
5510	24	PK		34-11	21-61-51	D03998		24			D40534P	B18		YC053-YC058	
5510	24	PK		35-0	21-61-51	D03998		24			D40534P	B18		YC059-YL999, YR301-YR323, YR325-YR328	
5510	24	B6		35-0	21-61-21	D00618		3			D40534P	B18		YN231-YN501	
5511	24	PK		35-6	21-61-51	D03998		19			D40534P	B15		YC051-YC052	
5511	24	PK		34-11	21-61-51	D03998		19			D40534P	B15		YC053-YC058	
5511	24	PK		35-0	21-61-51	D03998		19			D40534P	B15		YC059-YL999, YR301-YR323, YR325-YR328	
5511	24	B6		35-0	21-61-21	D00618		5			D40534P	B15		YN231-YN501	
5512	24	B6		35-11	21-51-12	D00646		26			D40534P	A16		YC051-YC052	
5512	24	B6		35-4	21-51-12	D00646		26			D40534P	A16		YC053-YC055	
5512	24	B6		35-3	21-51-12	D00646		26			D40534P	A16		YC056-YC058, YC065-YL999, YR301-YR323, YR325-YR328	
5512	24	B6		35-2	21-51-12	D00646		26			D40534P	A16		YC059-YC064	
5512	24	B6		35-0	21-61-21	D00618		2			D40534P	A16		YN231-YN501	
5513	24	PK		35-7	21-61-51	D03996		24			D40534P	B16		YC051-YC052	
5513	24	PK		35-1	21-61-51	D03996		24			D40534P	B16		YC053-YC055, YC059-YL999, YR301-YR323, YR325-YR328	
5513	24	PK		35-0	21-61-51	D03996		24			D40534P	B16		YC056-YC058	
5513	24	B6		35-0	21-61-21	D00618		1			D40534P	B16		YN231-YN501	
5514	24	PK		35-11	21-61-12	D00646		48			D40534P	A17		YC051-YC052	
5514	24	PK		35-4	21-61-12	D00646		48			D40534P	A17		YC053-YC055	
5514	24	PK		35-3	21-61-12	D00646		48			D40534P	A17		YC056-YC058, YC065-YL999, YR301-YR323, YR325-YR328	
5514	24	PK		35-2	21-61-12	D00646		48			D40534P	A17		YC059-YC064	
5514	24	B6		35-0	21-61-21	D00618		4			D40534P	A17		YN231-YN501	

WIRE LIST

D280A108

91-21-11

Section W2210

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2216	286A2216				P5 OVHD PANEL TO EE BAY (E4-1) RA2 (continued)										
5515	24		PK		3-7	21-61-11	D10956			1	TB0504Y	A005	1A		YC051-YC052
5515	24		PK		4-5	21-61-11	D10956			1	TB0504Y	A005	1A		YC053-YC058, YC065-YL999, YR301-YR323, YR325-YR328
5515	24		PK		4-3	21-61-11	D10956			1	TB0504Y	A005	1A		YC059-YC064
5515	22		CQ		4-5	21-61-21	D10956			1	TB0504Y	A005	1A		YN231-YN501
5516	20		PA		2-4	21-61-11	D10956			3	GD00261	ST..	1A		YC051-YL999, YR301-YR323, YR325-YR328
5516	20		CQ		2-4	21-61-21	D10956			3	GD00261	ST..	1A		YN231-YN501
5517	20		PA		2-4	21-61-11	D10956			2	GD00261	AC..	1A		YC051-YL999, YR301-YR323, YR325-YR328
5517	20		CQ		2-4	21-61-21	D10956			2	GD00261	AC..	1A		YN231-YN501
5518	22		CQ		32-10	21-61-21	D10958			1	D40534P	B17			YN231-YN501
5519	24		PK		35-11	21-61-14	D00646			51	D40534P	A18			YC051-YC052
5519	24		PK		35-4	21-61-14	D00646			51	D40534P	A18			YC053-YC055
5519	24		PK		35-3	21-61-14	D00646			51	D40534P	A18			YC056-YC058, YC065-YL999, YR301-YR323, YR325-YR328
5519	24		PK		35-2	21-61-14	D00646			51	D40534P	A18			YC059-YC064
5519	22		CQ		32-10	21-61-21	D10958			3	D40534P	A18			YN231-YN501
5520	24		B6		6-7	21-61-21	D00656			15	D40532P	20			YN231-YN501
5521	24		PK		4-7	21-61-14	D00646			52	TB0504Y	B009	1A		YC051-YC052
5521	24		PK		4-3	21-61-14	D00646			52	TB0504Y	B009	1A		YC053-YC058
5521	24		PK		4-5	21-61-14	D00646			52	TB0504Y	B009	1A		YC059-YC064
5521	24		PK		4-8	21-61-14	D00646			52	TB0504Y	B009	1A		YC065-YL999, YR301-YR323, YR325-YR328
5521	24		B6		4-10	21-61-21	D00680			31	TB0504Y	B009	1A		YN231-YN501
5522	24		PK		33-5	21-61-14	TB0504Y			B009	D40534P	A19			YC051-YC052
5522	24		PK		32-11	21-61-14	TB0504Y			B009	D40534P	A19			YC053-YC058
5522	24		PK		32-10	21-61-14	TB0504Y			B009	D40534P	A19			YC059-YC064
5522	24		PK		33-0	21-61-14	TB0504Y			B009	D40534P	A19			YC065-YL999, YR301-YR323, YR325-YR328
5522	24		B6		33-0	21-61-21	TB0504Y			B009	D40534P	A19			YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W2210

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W2216	286A2216				P5 OVHD PANEL TO EE BAY (E4-1) RA2 (continued)											
5523	24	B6			35-11	21-51-14	D00646	28				D40534P	A04		YC051-YC052	
5523	24	B6			35-4	21-51-14	D00646	28				D40534P	A04		YC053-YC055	
5523	24	B6			35-3	21-51-14	D00646	28				D40534P	A04		YC056-YC058, YC065-YR323, YR325-YR328	
5523	24	B6			35-2	21-51-14	D00646	28				D40534P	A04		YC059-YC064	
5524	22	CQ			20-11	21-27-31	S00870	2	C			D46112P	1		YC051-YC052	
5524	22	CQ			20-6	21-27-31	S00870	2	C			D46112P	1		YC053-YC058	
5524	22	CQ			20-7	21-27-31	S00870	2	C			D46112P	1		YC059-YC064	
5524	22	CQ			20-8	21-27-31	S00870	2	C			D46112P	1		YC065-YR323, YR325-YR328	
5525	22	CQ			4-1	21-27-31	S00870	3	C			GD00507	DC..	1A	YC051-YC052	
5525	22	CQ			3-11	21-27-31	S00870	3	C			GD00517	DC..	1A	YC053-YC064	
5525	22	CQ			4-0	21-27-31	S00870	3	C			GD00517	DC..	1A	YC065-YR323, YR325-YR328	
5526	24	B6			35-4	21-61-21	D00656	5				D40534P	B19		YN231-YN501	
5527	20	CQ			2-7	21-51-12	D00646	15				GD00504	DC..	1A	YC051-YC052	
5527	20	CQ			2-5	21-51-12	D00646	15				GD00518	DC..	1A	YC053-YC058	
5527	20	CQ			2-3	21-51-12	D00646	15				GD00518	DC..	1A	YC059-YL999, YR301-YR323, YR325-YR328	
5527	20	CQ			2-4	21-61-21	D00656	3				GD00518	DC..	1A	YN231-YN501	
5528	24	B6			4-8	21-51-12	D00646	10				TB0504Y	B007	1A	YC051-YC052	
5528	24	B6			4-4	21-51-12	D00646	10				TB0504Y	B007	1A	YC053-YC058	
5528	24	B6			4-5	21-51-12	D00646	10				TB0504Y	B007	1A	YC059-YC064	
5528	24	B6			4-9	21-51-12	D00646	10				TB0504Y	B007	1A	YC065-YL999, YR301-YR323, YR325-YR328	
5528	24	B6			4-10	21-61-21	D00656	4				TB0504Y	B007	1A	YN231-YN501	
5529	24	PK			4-3	21-61-14	D03996	20				TB0504Y	B009	1A	YC051-YC052, YC059-YC064	
5529	24	PK			4-0	21-61-14	D03996	20				TB0504Y	B009	1A	YC053-YC058	
5529	24	PK			4-6	21-61-14	D03996	20				TB0504Y	B009	1A	YC065-YL999, YR301-YR323, YR325-YR328	
5529	24	B6			4-9	21-61-21	D00656	13				TB0504Y	B009	1A	YN231-YN501	
5530	24	B6			33-6	21-51-12	TB0504Y	B007	1A			D40534P	A20		YC051-YC052	
5530	24	B6			33-0	21-51-12	TB0504Y	B007	1A			D40534P	A20		YC053-YC058	
5530	24	B6			32-11	21-51-12	TB0504Y	B007	1A			D40534P	A20		YC059-YC064	

WIRE LIST

D280A108

91-21-11

Section W2210

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2216	286A2216				P5 OVHD PANEL TO EE BAY (E4-1) RA2 (continued)										
5530	24		B6		33-1	21-51-12	TB0504Y	B007	1A		D40534P	A20			YC065-YL999, YR301-YR323, YR325-YR328
5530	24		B6		33-1	21-61-21	TB0504Y	B007	1A		D40534P	A20			YN231-YN501
5531	24		PK		4-9	36-11-11	D00646		43		TB0506Y	A009	1A		YN231-YN501
5532	24		PK		4-9	36-11-11	D00646		36		TB0506Y	A009	1A		YN231-YN501
5533	24		B6		19-9	36-11-11	D00646		33		D46112P		14		YC051-YC052
5533	24		B6		19-1	36-11-11	D00646		33		D46112P		14		YC053-YC058
5533	24		B6		19-0	36-11-11	D00646		33		D46112P		14		YC059-YR323, YR325-YR328
5534	24		B6		35-11	36-11-11	D00646		11		D40534P	B04			YC051-YC052
5534	24		B6		35-4	36-11-11	D00646		11		D40534P	B04			YC053-YC055
5534	24		B6		35-3	36-11-11	D00646		11		D40534P	B04			YC056-YC058, YC065-YR323, YR325-YR328
5534	24		B6		35-2	36-11-11	D00646		11		D40534P	B04			YC059-YC064
5535	24		B6		35-11	36-11-11	D00646		19		D40534P	A05			YC051-YC052
5535	24		B6		35-4	36-11-11	D00646		19		D40534P	A05			YC053-YC055
5535	24		B6		35-3	36-11-11	D00646		19		D40534P	A05			YC056-YC058, YC065-YR323, YR325-YR328
5535	24		B6		35-2	36-11-11	D00646		19		D40534P	A05			YC059-YC064
5536	24		B6		19-9	36-11-11	D00646		18		D46112P		15		YC051-YC052
5536	24		B6		19-1	36-11-11	D00646		18		D46112P		15		YC053-YC058
5536	24		B6		19-0	36-11-11	D00646		18		D46112P		15		YC059-YR323, YR325-YR328
5537	24		B6		24-4	36-11-11	D46112P		16		D40534P	B05			YC051-YC052
5537	24		B6		24-5	36-11-11	D46112P		16		D40534P	B05			YC053-YC064
5537	24		B6		24-6	36-11-11	D46112P		16		D40534P	B05			YC065-YR323, YR325-YR328
5538	24		PK		35-11	36-11-11	D00646		44		D40534P	A06			YC051-YC052
5538	24		PK		35-4	36-11-11	D00646		44		D40534P	A06			YC053-YC055
5538	24		PK		35-3	36-11-11	D00646		44		D40534P	A06			YC056-YC058, YC065-YR323, YR325-YR328
5538	24		PK		35-2	36-11-11	D00646		44		D40534P	A06			YC059-YC064
5539	24		PK		35-11	36-11-11	D00646		21		D40534P	B06			YC051-YC052
5539	24		PK		35-4	36-11-11	D00646		21		D40534P	B06			YC053-YC055

WIRE LIST
D280A108

91-21-11
Section W2210
Page 11
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W2216	286A2216				P5 OVHD PANEL TO EE BAY (E4-1) RA2 (continued)												
5539	24		PK		35-3		36-11-11	D00646		21			D40534P		B06		YC056-YC058, YC065-YR323, YR325-YR328
5539	24		PK		35-2		36-11-11	D00646		21			D40534P		B06		YC059-YC064
5540	24		PK		35-11		36-11-11	D00646		22			D40534P		A07		YC051-YC052
5540	24		PK		35-4		36-11-11	D00646		22			D40534P		A07		YC053-YC055
5540	24		PK		35-3		36-11-11	D00646		22			D40534P		A07		YC056-YC058, YC065-YR323, YR325-YR328
5540	24		PK		35-2		36-11-11	D00646		22			D40534P		A07		YC059-YC064
5541	24		B6		6-10		36-11-11	D00646		20			D40532P		4		YC051-YC052
5541	24		B6		6-7		36-11-11	D00646		20			D40532P		4		YC053-YC058
5541	24		B6		6-6		36-11-11	D00646		20			D40532P		4		YC059-YR323, YR325-YR328
5542	18		PA		7-11		33-12-11	T00031		HV	D		D40532P		21	18	YC051-YC064
5542	18		PA		8-0		33-12-11	T00031		HV	D		D40532P		21	18	YC065-YR323, YR325-YR328
5543	10		PA		7-7		33-12-11	T00031		G	D		GD01018		AC..	E	YC051-YC052
5543	10		PA		8-3		33-12-11	T00031		G	D		GD01018		AC..	E	YC053-YR323, YR325-YR328
5544	10		PA		10-8		33-12-11	T00031		LV	D		TB5060B		1	E	YC051-YC052
5544	10		PA		9-10		33-12-11	T00031		LV	D		TB5060B		1	E	YC053-YC058, YC065-YR323, YR325-YR328
5544	10		PA		9-9		33-12-11	T00031		LV	D		TB5060B		1	E	YC059-YC064
5545	22		CQ		19-2		30-31-12	D00638		38			D46112P		3		YC051-YC052
5545	22		CQ		18-6		30-31-12	D00638		38			D46112P		3		YC053-YC058
5545	22		CQ		18-7		30-31-12	D00638		38			D46112P		3		YC059-YR323, YR325-YR328
5546	22		CQ		19-2		30-31-12	D00638		44			D46112P		4		YC051-YC052
5546	22		CQ		18-6		30-31-12	D00638		44			D46112P		4		YC053-YC058
5546	22		CQ		18-7		30-31-12	D00638		44			D46112P		4		YC059-YR323, YR325-YR328
5547	22		CQ		19-2		30-31-12	D00638		45			D46112P		5		YC051-YC052
5547	22		CQ		18-6		30-31-12	D00638		45			D46112P		5		YC053-YC058
5547	22		CQ		18-7		30-31-12	D00638		45			D46112P		5		YC059-YR323, YR325-YR328
5548	22		CQ		19-2		30-31-12	D00638		41			D46112P		6		YC051-YC052
5548	22		CQ		18-6		30-31-12	D00638		41			D46112P		6		YC053-YC058

WIRE LIST

D280A108

91-21-11

Section W2210

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To				Effectivity
Wire No.	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W2216	286A2216			P5 OVHD PANEL TO EE BAY (E4-1) RA2 (continued)											
5548	22		CQ		18-7	30-31-12	D00638		41		D46112P		6		YC059-YR323, YR325-YR328
5549	24		B6		33-7	21-51-12	D41812P		A01		TB0504Y	B007	1A		YC051-YC052
5549	24		B6		33-1	21-51-12	D41812P		A01		TB0504Y	B007	1A		YC053-YC058, YC065-YL999, YR301-YR323, YR325-YR328
5549	24		B6		32-11	21-51-12	D41812P		A01		TB0504Y	B007	1A		YC059-YC064
5550	20		CQ		2-0	30-31-12	D00638		55		GD00504	DC..	1A		YC051-YC052
5550	20		CQ		1-10	30-31-12	D00638		55		GD00518	DC..	1A		YC053-YR323, YR325-YR328
5552	24		B6		36-0	21-51-12	D00646		12		D41812P	A03			YC051-YC052
5552	24		B6		35-4	21-51-12	D00646		12		D41812P	A03			YC053-YC058
5552	24		B6		35-3	21-51-12	D00646		12		D41812P	A03			YC059-YL999, YR301-YR323, YR325-YR328
5553	24		PK		35-8	21-61-11	D41812P		A04		D03996		8		YC051-YC052
5553	24		PK		35-1	21-61-11	D41812P		A04		D03996		8		YC053-YL999, YR301-YR323, YR325-YR328
5554	20		PA		32-9	23-32-11	D40532P		15		D40534P	A08			YN236-YN260
5555	24		B6		36-0	21-51-12	D41812P		A02		D00646	55			YC051-YC052
5555	24		B6		35-4	21-51-12	D41812P		A02		D00646	55			YC053-YC058
5555	24		B6		35-3	21-51-12	D41812P		A02		D00646	55			YC059-YL999, YR301-YR323, YR325-YR328
5558	24		PK		36-0	21-61-12	D41812P		B02		D00646	27			YC051-YC052
5558	24		PK		35-4	21-61-12	D41812P		B02		D00646	27			YC053-YC058
5558	24		PK		35-3	21-61-12	D41812P		B02		D00646	27			YC059-YL999, YR301-YR323, YR325-YR328
5560	20		PA		2-3	21-61-11	D03996		12		GD00504	DC..	1A		YC051-YC052
5560	20		PA		2-2	21-61-11	D03996		12		GD00518	DC..	1A		YC053-YL999, YR301-YR323, YR325-YR328
5561	20		PA		2-3	21-61-11	D03996		19		GD00504	ST..	1A		YC051-YC052
5561	20		PA		2-2	21-61-11	D03996		19		GD00518	ST..	1A		YC053-YL999, YR301-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W2210

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W2216	286A2216				P5 OVHD PANEL TO EE BAY (E4-1) RA2 (continued)											
5562	24		PK		36-0	21-61-14	D41812P		A15			D00646	16			YC051-YC052
5562	24		PK		35-4	21-61-14	D41812P		A15			D00646	16			YC053-YC058
5562	24		PK		35-3	21-61-14	D41812P		A15			D00646	16			YC059-YL999, YR301-YR323, YR325-YR328
5563	24		PK		35-8	21-61-14	D41812P		A11			D03996	18			YC051-YC052
5563	24		PK		35-1	21-61-14	D41812P		A11			D03996	18			YC053-YL999, YR301-YR323, YR325-YR328
5564	20		PA		2-3	21-61-14	D03996		17			GD00504	DC..	1A		YC051-YC052
5564	20		PA		2-2	21-61-14	D03996		17			GD00518	DC..	1A		YC053-YL999, YR301-YR323, YR325-YR328
5601	18		GA		4-5	33-12-11	D40532P		1	18		D40566P	S	18		YC051-YC052
5601	18		PA		4-1	33-12-11	D40532P		1	18		TB0502V	A005	1		YC053-YC058
5601	18		PA		4-0	33-12-11	D40532P		1	18		TB0502V	A005	1		YC059-YC064
5601	18		PA		4-3	33-12-11	D40532P		1	18		TB0502V	A005	1		YC065-YR323, YR325-YR328
5602	20		GA		4-7	33-12-11	D00638		57			D40566P	GG			YC051-YC052
5602	20		PA		2-4	33-12-11	D00638		57			TB0508Z	A013	1A		YC053-YC058
5602	20		PA		2-0	33-12-11	D00638		57			TB0508Z	A013	1A		YC059-YR323, YR325-YR328
5603	20		GA		4-7	33-12-11	D00638		54			D40566P	S-			YC051-YC052
5603	20		PA		2-0	33-12-11	D00638		54			GD00520	AC..	1A		YC053-YC058
5603	20		PA		1-11	33-12-11	D00638		54			GD00520	AC..	1A		YC059-YR323, YR325-YR328
5604	20		GA		6-6	33-12-11	D00786		1			D40566P	AA			YC051-YC052
5604	20		PA		3-10	33-12-11	D00786		1			TB0508Z	A013	1A		YC053-YC058
5604	20		PA		3-5	33-12-11	D00786		1			TB0508Z	A013	1A		YC059-YR323, YR325-YR328
5605	20		GA		6-6	33-12-11	D00786		2			D40566P	CC			YC051-YC052
5605	20		PA		3-6	33-12-11	D00786		2			GD00520	AC..	1A		YC053-YC058
5605	20		PA		3-4	33-12-11	D00786		2			GD00520	AC..	1A		YC059-YR323, YR325-YR328
5606	20		GA		6-2	33-12-11	D02486		2			D40566P	Z-			YC051-YC052
5606	20		PA		3-5	33-12-11	D02486		2			TB0508Z	A013	1A		YC053-YC058
5606	20		PA		3-0	33-12-11	D02486		2			TB0508Z	A013	1A		YC059-YR323, YR325-YR328
5607	20		GA		6-2	33-12-11	D02486		1			D40566P	C-			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W2210

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W2216	286A2216				P5 OVHD PANEL TO EE BAY (E4-1) RA2 (continued)											
5607	20	PA			3-1	33-12-11		D02486		1		GD00520	AC..	1A		YC053-YC058
5607	20	PA			2-11	33-12-11		D02486		1		GD00520	AC..	1A		YC059-YR323, YR325-YR328
5608	20	GA			6-6	33-12-11		D00654		2		D40566P	FF			YC051-YC052
5608	20	PA			3-9	33-12-11		D00654		2		TB0508Z	A013	1A		YC053-YC058
5608	20	PA			3-5	33-12-11		D00654		2		TB0508Z	A013	1A		YC059-YR323, YR325-YR328
5609	20	GA			6-6	33-12-11		D00654		1		D40566P	EE			YC051-YC052
5609	20	PA			3-6	33-12-11		D00654		1		GD00520	AC..	1A		YC053-YC058
5609	20	PA			3-4	33-12-11		D00654		1		GD00520	AC..	1A		YC059-YR323, YR325-YR328
5610	20	GA			6-8	33-12-11		D00794		1		D40566P	R			YC051-YC052
5610	20	PA			3-11	33-12-11		D00794		1		TB0508Z	A013	1A		YC053-YC058
5610	20	PA			3-7	33-12-11		D00794		1		TB0508Z	A013	1A		YC059-YR323, YR325-YR328
5611	20	GA			6-8	33-12-11		D00794		2		D40566P	F			YC051-YC052
5611	20	PA			3-7	33-12-11		D00794		2		GD00520	AC..	1A		YC053-YC058
5611	20	PA			3-6	33-12-11		D00794		2		GD00520	AC..	1A		YC059-YR323, YR325-YR328
5612	20	GA			4-3	33-12-11		GD00509	AC..	1A		D40566P	G			YC051-YC052
5651	18	GA			4-5	33-12-11		D40532P		2	18	D40566P	A	18		YC051-YC052
5651	18	PA			4-1	33-12-11		D40532P		2	18	TB0502V	B005	1		YC053-YC058
5651	18	PA			4-0	33-12-11		D40532P		2	18	TB0502V	B005	1		YC059-YC064
5651	18	PA			4-3	33-12-11		D40532P		2	18	TB0502V	B005	1		YC065-YR323, YR325-YR328
5652	20	GA			4-9	33-12-11		D03998		23		D40566P	B			YC051-YC052
5652	20	PA			2-7	33-12-11		D03998		23		TB0508Z	B013	1A		YC053-YC058
5652	20	PA			2-2	33-12-11		D03998		23		TB0508Z	B013	1A		YC059-YL999, YR301-YR323, YR325-YR328
5652	20	PA			2-6	33-12-11		D00656		2		TB0508Z	B013	1A		YN231-YN501
5653	20	GA			4-9	33-12-11		D03998		2		D40566P	L			YC051-YC052
5653	20	PA			2-3	33-12-11		D03998		2		GD00520	AC..	1A		YC053-YC058
5653	20	PA			2-2	33-12-11		D03998		2		GD00520	AC..	1A		YC059-YL999, YR301-YR323, YR325-YR328
5653	20	PA			2-5	33-12-11		D00656		1		GD00520	AC..	1A		YN231-YN501
5654	20	GA			4-11	33-12-11		D00090		6		D40566P	C			YC051-YC052
5654	20	PA			2-9	33-12-11		D00090		6		TB0508Z	B013	1A		YC053-YC058

WIRE LIST

D280A108

91-21-11

Section W2210

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W2216	286A2216	P5 OVHD PANEL TO EE BAY (E4-1) RA2 (continued)													
5654	20 PA		2-3	33-12-11	D00090	6			TB0508Z	B013	1A		YC059-YR323, YR325-YR328		
5655	20 GA		4-11	33-12-11	D00090	7			D40566P	M			YC051-YC052		
5655	20 PA		2-5	33-12-11	D00090	7			GD00520	AC..	1A		YC053-YC058		
5655	20 PA		2-2	33-12-11	D00090	7			GD00520	AC..	1A		YC059-YR323, YR325-YR328		
5656	20 PA		2-2	33-12-11	D00618	7			TB0508Z	B013	1A		YN231-YN501		
5657	20 PA		2-2	33-12-11	D00618	12			GD00520	AC..	1A		YN231-YN501		
5658	20 GA		5-2	33-12-11	D00646	2			D40566P	W			YC051-YC052		
5658	20 PA		2-11	33-12-11	D00646	2			TB0508Z	B013	1A		YC053-YC058		
5658	20 PA		2-5	33-12-11	D00646	2			TB0508Z	B013	1A		YC059-YR323, YR325-YR328		
5659	20 GA		5-2	33-12-11	D00646	1			D40566P	J			YC051-YC052		
5659	20 PA		2-8	33-12-11	D00646	1			GD00520	AC..	1A		YC053-YC058		
5659	20 PA		2-4	33-12-11	D00646	1			GD00520	AC..	1A		YC059-YR323, YR325-YR328		
5660	20 PA		2-5	33-12-11	D00620	7			TB0508Z	B013	1A		YN231-YN501		
5661	20 PA		2-5	33-12-11	D00620	12			GD00520	AC..	1A		YN231-YN501		
5662	20 GA		6-0	33-12-11	D00096	1			D40566P	X			YC051-YC052		
5662	20 PA		3-3	33-12-11	D00096	1			TB0508Z	B013	1A		YC053-YC058		
5662	20 PA		3-1	33-12-11	D00096	1			TB0508Z	B013	1A		YC059-YC064		
5662	20 PA		3-0	33-12-11	D00096	1			TB0508Z	B013	1A		YC065-YR323, YR325-YR328		
5663	20 GA		6-0	33-12-11	D00096	2			D40566P	H			YC051-YC052		
5663	20 PA		2-11	33-12-11	D00096	2			GD00520	AC..	1A		YC053-YC058		
5663	20 PA		3-1	33-12-11	D00096	2			GD00520	AC..	1A		YC059-YC064		
5663	20 PA		3-0	33-12-11	D00096	2			GD00520	AC..	1A		YC065-YR323, YR325-YR328		
5664	20 GA		6-6	33-12-11	D10726	24			D40566P	Y			YC051-YC052		
5664	20 PA		3-8	33-12-11	D10726	24			TB0508Z	B013	1A		YC053-YC058		
5664	20 PA		3-4	33-12-11	D10726	24			TB0508Z	B013	1A		YC059-YR323, YR325-YR328		
5665	20 GA		6-6	33-12-11	D10726	13			D40566P	E-			YC051-YC052		
5665	20 PA		3-4	33-12-11	D10726	13			GD00520	AC..	1A		YC053-YR323, YR325-YR328		
5666	20 GA		4-3	33-12-11	GD00509	AC..	1A		D40566P	K			YC051-YC052		
5701	18 GA		4-5	33-12-11	D40532P	3	18		D40568P	S	18		YC051-YC052		
5701	18 PA		4-3	33-12-11	D40532P	3	18		TB0501V	A031	1		YC053-YC058		
5701	18 PA		4-2	33-12-11	D40532P	3	18		TB0501V	A031	1		YC059-YC064		

WIRE LIST

D280A108

91-21-11

Section W2210

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2216	286A2216				P5 OVHD PANEL TO EE BAY (E4-1) RA2 (continued)										
5701	18		PA		4-5	33-12-11	D40532P	3	18		TB0501V	A031	1		YC065-YR323, YR325-YR328
5702	20		GA		5-5	33-12-11	D00553	1			D40568P	GG			YC051-YC052
5702	20		PA		3-3	33-12-11	D00553	1			TB0507Z	A013	1A		YC053-YC055
5702	20		PA		3-2	33-12-11	D00553	1			TB0507Z	A013	1A		YC056-YC058
5702	20		PA		2-9	33-12-11	D00553	1			TB0507Z	A013	1A		YC059-YR323, YR325-YR328
5703	20		GA		5-5	33-12-11	D00553	2			D40568P	S-			YC051-YC052
5703	20		PA		2-9	33-12-11	D00553	2			GD00519	AC..	1A		YC053-YC058
5703	20		PA		2-10	33-12-11	D00553	2			GD00519	AC..	1A		YC059-YR323, YR325-YR328
5704	20		GA		6-2	33-12-11	D00616	6			D40568P	R			YC051-YC052
5704	20		PA		3-7	33-12-11	D00616	6			TB0507Z	A013	1A		YC053-YC058
5704	20		PA		2-11	33-12-11	D00616	6			TB0507Z	A013	1A		YC059-YC064
5704	20		PA		3-0	33-12-11	D00616	6			TB0507Z	A013	1A		YC065-YR323, YR325-YR328
5705	20		GA		6-2	33-12-11	D00616	7			D40568P	F			YC051-YC052
5705	20		PA		3-1	33-12-11	D00616	7			GD00519	AC..	1A		YC053-YC058, YC065-YR323, YR325-YR328
5705	20		PA		3-0	33-12-11	D00616	7			GD00519	AC..	1A		YC059-YC064
5706	20		GA		4-11	33-12-11	D00624	2			D40568P	FF			YC051-YC052
5706	20		PA		2-10	33-12-11	D00624	2			TB0507Z	A013	1A		YC053-YC055
5706	20		PA		2-9	33-12-11	D00624	2			TB0507Z	A013	1A		YC056-YC058
5706	20		PA		2-4	33-12-11	D00624	2			TB0507Z	A013	1A		YC059-YR323, YR325-YR328
5707	20		GA		4-11	33-12-11	D00624	1			D40568P	EE			YC051-YC052
5707	20		PA		2-4	33-12-11	D00624	1			GD00519	AC..	1A		YC053-YC058
5707	20		PA		2-5	33-12-11	D00624	1			GD00519	AC..	1A		YC059-YR323, YR325-YR328
5708	20		GA		6-4	33-12-11	D00626	15			D40568P	AA			YC051-YC052
5708	20		PA		3-9	33-12-11	D00626	15			TB0507Z	A013	1A		YC053-YC055
5708	20		PA		3-8	33-12-11	D00626	15			TB0507Z	A013	1A		YC056-YC058
5708	20		PA		3-2	33-12-11	D00626	15			TB0507Z	A013	1A		YC059-YR323, YR325-YR328
5709	20		GA		6-4	33-12-11	D00626	16			D40568P	CC			YC051-YC052
5709	20		PA		3-2	33-12-11	D00626	16			GD00519	AC..	1A		YC053-YC058
5709	20		PA		3-3	33-12-11	D00626	16			GD00519	AC..	1A		YC059-YR323, YR325-YR328

WIRE LIST
D280A108

91-21-11
Section W2210
Page 17
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W2216	286A2216				P5 OVHD PANEL TO EE BAY (E4-1) RA2 (continued)											
5710	20		GA		4-3	33-12-11		GD00509	AC..	1A		D40568P	G			YC051-YC052
5712	20		PA		4-7	33-12-11		TB0502V	A005	1		TB0508Z	A013	1A		YC053-YC058
5712	20		PA		4-2	33-12-11		TB0502V	A005	1		TB0508Z	A013	1A		YC059-YC064
5712	20		PA		4-6	33-12-11		TB0502V	A005	1		TB0508Z	A013	1A		YC065-YR323, YR325-YR328
5713	20		PA		4-4	33-12-11		TB0501V	A031	1		TB0507Z	A013	1A		YC053-YC055
5713	20		PA		4-3	33-12-11		TB0501V	A031	1		TB0507Z	A013	1A		YC056-YC058
5713	20		PA		4-1	33-12-11		TB0501V	A031	1		TB0507Z	A013	1A		YC059-YC064
5713	20		PA		4-6	33-12-11		TB0501V	A031	1		TB0507Z	A013	1A		YC065-YR323, YR325-YR328
5714	20		PA		4-7	33-12-11		TB0502V	B005	1		TB0508Z	B013	1A		YC053-YC058
5714	20		PA		4-2	33-12-11		TB0502V	B005	1		TB0508Z	B013	1A		YC059-YC064
5714	20		PA		4-6	33-12-11		TB0502V	B005	1		TB0508Z	B013	1A		YC065-YR323, YR325-YR328
6003	24		PK		4-6	34-61-17		D00648		8		TB0504X	B013	1A		YC051-YC052, YC059-YC064
6003	24		PK		4-2	34-61-17		D00648		8		TB0504X	B013	1A		YC053-YC058
6003	24		PK		4-7	34-61-17		D00648		8		TB0504X	B013	1A		YC065-YR323, YR325-YR328
6004	20		PA		2-7	34-61-17		D00648		18		GD00504	DC..	1A		YC051-YC052
6004	20		PA		2-5	34-61-17		D00648		18		GD00518	DC..	1A		YC053-YC064
6004	20		PA		2-4	34-61-17		D00648		18		GD00518	DC..	1A		YC065-YR323, YR325-YR328
6005	20		PA		2-5	34-61-17		D00680		38		GD00504	DC..	1A		YC051-YC052
6005	20		PA		2-3	34-61-17		D00680		38		GD00518	DC..	1A		YC053-YC058
6005	20		PA		2-5	34-61-17		D00680		38		GD00518	DC..	1A		YC059-YR323, YR325-YR328
6006	24		PK		4-4	34-61-17		D00680		39		TB0504X	A014	1A		YC051-YC052
6006	24		PK		4-0	34-61-17		D00680		39		TB0504X	A014	1A		YC053-YC058
6006	24		PK		4-5	34-61-17		D00680		39		TB0504X	A014	1A		YC059-YC064
6006	24		PK		4-9	34-61-17		D00680		39		TB0504X	A014	1A		YC065-YR323, YR325-YR328
6007	20		PA		1-11	73-21-12		D03172			AA	GD00508	ST..	1A		YC051-YC058
6007	20		PA		1-10	73-21-12		D03172			AA	GD00508	ST..	1A		YC059-YR323, YR325-YR328
6008	20		PA		1-11	73-21-12		D03172		18		GD00508	DC..	1A		YC051-YC058
6008	20		PA		1-10	73-21-12		D03172		18		GD00508	DC..	1A		YC059-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W2210

Page 18

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2218	286A2218				P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2											
0001	22		PA		14-8	23-42-11		S00036		1	C	D40170P		5		YC051-YC052
0001	22		PA		14-2	23-42-11		S00036		1	C	D40170P		5		YC053-YC064
0001	22		PA		14-11	23-42-11		S00036		1	C	D40170P		5		YC065-YR328
0002	22		PA		11-1	23-42-11		TB0505Y	B007	1A		D40170P		6		YC051-YC052
0002	22		PA		10-8	23-42-11		TB0505Y	B007	1A		D40170P		6		YC053-YC058
0002	22		PA		10-7	23-42-11		TB0505Y	B007	1A		D40170P		6		YC059-YD170
0002	22		PA		16-7	23-42-11		SP00595			9	D40170P		6		YL951-YN260
0003	22		PA		33-3	23-42-11		D40542P	A02			D40170P		15		YC051-YC052, YC056-YD157
0003	22		PA		33-6	23-42-11		D40542P	A02			D40170P		15		YC053-YC055
0003	22		PA		10-8	23-42-11		TB0506Y	B005	1A		D40170P		15		YD158-YR328
0004	22		PA		11-0	23-42-11		D40170P		16		D40536P		31		YC051-YC052
0004	22		PA		10-7	23-42-11		D40170P		16		D40536P		31		YC053-YR328
0005	22		PA		10-9	23-42-11		TB0506X	A013	1A		D40170P		30		YC051-YC052
0005	22		PA		10-7	23-42-11		TB0506X	A013	1A		D40170P		30		YC053-YC058
0005	22		PA		10-5	23-42-11		TB0506X	A013	1A		D40170P		30		YC059-YC064
0005	22		PA		10-6	23-42-11		TB0506X	A013	1A		D40170P		30		YC065-YR328
0006	22		PA		4-5	23-43-11		TB0505Y	B007	1A		D40536P		19		YC051-YC052
0006	22		PA		4-1	23-43-11		TB0505Y	B007	1A		D40536P		19		YC053-YC058, YC065-YD170
0006	22		PA		4-0	23-43-11		TB0505Y	B007	1A		D40536P		19		YC059-YC064
0006	22		PA		12-1	23-43-11		SP00595		9		D40536P		19		YL951-YR328
0007	22		PA		28-5	23-43-11		D40542P	A01			D40536P		7		YC051-YC052
0007	22		PA		27-5	23-43-11		D40542P	A01			D40536P		7		YC053-YC055
0007	22		PA		27-2	23-43-11		D40542P	A01			D40536P		7		YC056-YD157
0007	22		PA		4-2	23-43-11		TB0506Y	B005	1A		D40536P		7		YD158-YR328
0009	22		PA		1-4	23-43-11		S00036		2	C	S00032		1	C	YC051-YC064
0009	22		PA		1-3	23-43-11		S00036		2	C	S00032		1	C	YC065-YR328
0010	22		PA		6-10	23-43-11		S00036		2	C	TB0505Y	B007	1A		YC051-YC052
0010	22		PA		6-3	23-43-11		S00036		2	C	TB0505Y	B007	1A		YC053-YC058
0010	22		PA		6-6	23-43-11		S00036		2	C	TB0505Y	B007	1A		YC059-YC064
0010	22		PA		7-6	23-43-11		S00036		2	C	TB0505Y	B007	1A		YC065-YD170
0010	22		PA		16-5	23-43-11		S00036		2	C	SP00595		9		YL951-YR328
0011	22		PA		3-6	23-42-11		TB0505Y	B007	1A		D40538P		7		YC051-YC052
0011	22		PA		3-5	23-42-11		TB0505Y	B007	1A		D40538P		7		YC053-YC058, YC065-YD170
0011	22		PA		3-4	23-42-11		TB0505Y	B007	1A		D40538P		7		YC059-YC064
0011	22		PA		11-8	23-42-11		SP00595		9		D40538P		7		YL951-YR328
0012	24		PK		3-8	23-24-11		D40536P		4		TB0261X	B013	1A		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W2210

Page 19

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W2218	286A2218				P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)												
0012	24		PK		3-2	23-24-11		D40536P	4			TB0261X	B013	1A		YC053-YC064	
0012	24		PK		3-7	23-24-11		D40536P	4			TB0261X	B013	1A		YC065-YD170	
0013	24		PK		1-4	33-25-11		S00045	2	C		S00045	6	C		YC051-YD157	
0014	24		PK		8-2	33-25-11		S00045	5	C		D40536P	18			YC051-YC052	
0014	24		PK		7-10	33-25-11		S00045	5	C		D40536P	18			YC053-YC064	
0014	24		PK		7-11	33-25-11		S00045	5	C		D40536P	18			YC065-YD157, YN231-YN235	
0014	24		PK		7-11	33-25-11		S00045	5	C	*	D40536P	18			YD158-YL999, YN236-YR328	
0015	20		PA		4-0	33-25-11		S00045	4	C		GD00501	DC..	1A		YC051-YC052, YC059-YR328	
0015	20		PA		3-11	33-25-11		S00045	4	C		GD00501	DC..	1A		YC053-YC058	
0016	20		PA		4-0	33-25-11		S00046	4	C		GD00501	DC..	1A		YC051-YC052, YC059-YR328	
0016	20		PA		3-11	33-25-11		S00046	4	C		GD00501	DC..	1A		YC053-YC058	
0017	24		PK		8-2	33-25-11		S00046	5	C		D40536P	9			YC051-YC052	
0017	24		PK		7-10	33-25-11		S00046	5	C		D40536P	9			YC053-YD157, YN231-YN235	
0017	24		PK		7-10	33-25-11		S00046	5	C	*	D40536P	9			YD158-YL999, YN236-YR328	
0018	24		PK		1-4	33-25-11		S00046	6	C		S00046	2	C		YC051-YD170	
0018	24		PK		0-7	33-25-11		S00046	6	C		S00046	2	C		YL951-YR328	
0019	20		PA		3-8	33-25-11		D03072	B3			GD00501	DC..	1A		YC051-YC052	
0019	20		PA		3-9	33-25-11		D03072	B3			GD00501	DC..	1A		YC053-YR328	
0020	24		PK		7-11	33-25-11		D03072	X1			D40536P	30			YC051-YC052	
0020	24		PK		7-7	33-25-11		D03072	X1			D40536P	30			YC053-YC064	
0020	24		PK		7-8	33-25-11		D03072	X1			D40536P	30			YC065-YR328	
0021	20		PA		5-5	33-25-11		D03072	X2			TB0504X	B016	1A		YC051-YC052	
0021	20		PA		5-0	33-25-11		D03072	X2			TB0504X	B016	1A		YC053-YC058	
0021	20		PA		5-3	33-25-11		D03072	X2			TB0504X	B016	1A		YC059-YC064	
0021	20		PA		6-0	33-25-11		D03072	X2			TB0504X	B016	1A		YC065-YR328	
0022	24		PK		1-3	33-25-11		D03072	B2			S00046	1	C		ALL	
0024	20		PA		9-9	33-32-11		S00062	4	C	*	D40536P	26			YC051-YC052	
0024	20		PA		9-5	33-32-11		S00062	4	C	*	D40536P	26			YC053-YR328	
0025	20		PA		1-8	33-32-11		S00062	4	C	*	S00062	1	C		ALL	
0026	20		PA		9-9	33-32-11		S00062	5	C		D40536P	5			YC051-YC052	
0026	20		PA		9-5	33-32-11		S00062	5	C		D40536P	5			YC053-YR328	
0027	20		PA		9-9	33-32-11		S00062	2	C		D40536P	6			YC051-YC052	
0027	20		PA		9-5	33-32-11		S00062	2	C		D40536P	6			YC053-YR328	

WIRE LIST

D280A108

91-21-11

Section W2210

Page 20

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2218	286A2218				P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)										
0028	24		PK		7-3	33-25-11	S00045	1	C		D40538P	2			YC051-YC052
0028	24		PK		7-2	33-25-11	S00045	1	C		D40538P	2			YC053-YR328
0029	20		PA		3-10	33-51-11	S00007	1C	B		GD00501	DC..	1A		YC051-YC058
0029	20		PA		3-11	33-51-11	S00007	1C	B		GD00501	DC..	1A		YC059-YR328
0030	22		PA		6-5	33-51-11	S00007	1NO	B	*	TB0505Y	B001	1A		YC051-YC052
0030	22		PA		5-5	33-51-11	S00007	1NO	B	*	TB0505Y	B001	1A		YC053-YC058
0030	22		PA		6-2	33-51-11	S00007	1NO	B	*	TB0505Y	B001	1A		YC059-YC064
0030	22		PA		6-3	33-51-11	S00007	1NO	B	*	TB0505Y	B001	1A		YC065-YR328
0031	22		PA		1-4	33-51-11	S00007	1NO	B	*	S00007	5NO	B	*	YC051-YD170
0031	22		PA		0-7	33-51-11	S00007	1NO	B	*	S00007	5NO	B	*	YL951-YR328
0032	20		PA		3-10	33-51-11	S00007	5C	B		GD00501	DC..	1A		YC051-YC058
0032	20		PA		3-11	33-51-11	S00007	5C	B		GD00501	DC..	1A		YC059-YR328
0033	22		PA		14-2	33-51-11	S00007	5NO	B	*	D40170P	17			YC051-YC052
0033	22		PA		13-10	33-51-11	S00007	5NO	B	*	D40170P	17			YC053-YC058, YC065-YR328
0033	22		PA		13-9	33-51-11	S00007	5NO	B	*	D40170P	17			YC059-YC064
0034	22		PA		6-5	33-51-11	S00007	6NO	B		TB0505Y	B003	1A		YC051-YC052
0034	22		PA		5-5	33-51-11	S00007	6NO	B		TB0505Y	B003	1A		YC053-YC058
0034	22		PA		6-2	33-51-11	S00007	6NO	B		TB0505Y	B003	1A		YC059-YC064
0034	22		PA		6-3	33-51-11	S00007	6NO	B		TB0505Y	B003	1A		YC065-YR328
0035	22		PA		14-2	33-51-11	S00007	6C	B		D40170P	28			YC051-YC052
0035	22		PA		13-10	33-51-11	S00007	6C	B		D40170P	28			YC053-YC058, YC065-YR328
0035	22		PA		13-9	33-51-11	S00007	6C	B		D40170P	28			YC059-YC064
0036	20		PA		7-8	33-42-11	S00260	5	C		D40538P	10			YC051-YC052, YC065-YR328
0036	20		PA		7-7	33-42-11	S00260	5	C		D40538P	10			YC053-YC055, YC059-YC064
0036	20		PA		7-5	33-42-11	S00260	5	C		D40538P	10			YC056-YC058
0037	20		PA		8-7	33-43-11	S00058	3	C	*	D40538P	3			YC051-YC052
0037	20		PA		8-5	33-43-11	S00058	3	C	*	D40538P	3			YC053-YC064
0037	20		PA		8-6	33-43-11	S00058	3	C	*	D40538P	3			YC065-YR328
0038	20		PA		33-9	33-43-11	S00058	2	C		D40540P	A17			YC051-YC052
0038	20		PA		32-9	33-43-11	S00058	2	C		D40540P	A17			YC053-YC055
0038	20		PA		33-7	33-43-11	S00058	2	C		D40540P	A17			YC056-YC058, YC065-YR328
0038	20		PA		33-6	33-43-11	S00058	2	C		D40540P	A17			YC059-YC064
0039	20		PA		1-4	33-43-11	S00058	3	C	*	S00058	1	C		YC051-YC064
0039	20		PA		1-0	33-43-11	S00058	3	C	*	S00058	1	C		YC065-YR328

WIRE LIST

D280A108

91-21-11

Section W2210

Page 21

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2218	286A2218			P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)											
0041	24	PK		20-0	23-31-06	S00045		5	C	*	D46114P	21			YD158-YL999
0041	24	PK		20-0	23-31-06	D46114P		21			S00045	5	C	*	YN231-YN260
0041	24	PK		20-0	44-21-22	S00045		5	C	*	D46114P	21			YN501-YR328
0042	24	PK		20-0	23-31-06	S00046		5	C	*	D46114P	22			YD158-YL999
0042	24	PK		20-0	23-31-06	D46114P		22			S00046	5	C	*	YN231-YN260
0042	24	PK		20-0	44-21-22	S00046		5	C	*	D46114P	22			YN501-YR328
0045	22	PA		10-9	23-42-11	TB0506X	B013	1A			D40170P	27			YC051-YC052
0045	22	PA		10-7	23-42-11	TB0506X	B013	1A			D40170P	27			YC053-YC058
0045	22	PA		10-5	23-42-11	TB0506X	B013	1A			D40170P	27			YC059-YC064
0045	22	PA		10-6	23-42-11	TB0506X	B013	1A			D40170P	27			YC065-YD157
0055	22	PA		26-8	23-42-11	TB0506X	B013	1A			D40510P	B02			YC051-YC052
0055	22	PA		25-11	23-42-11	TB0506X	B013	1A			D40510P	B02			YC053-YC058
0055	22	PA		25-9	23-42-11	TB0506X	B013	1A			D40510P	B02			YC059-YC064
0055	22	PA		25-10	23-42-11	TB0506X	B013	1A			D40510P	B02			YC065-YD157
0056	22	PA		26-8	23-42-11	TB0506X	A013	1A			D40510P	A02			YC051-YC052
0056	22	PA		25-11	23-42-11	TB0506X	A013	1A			D40510P	A02			YC053-YC058
0056	22	PA		25-9	23-42-11	TB0506X	A013	1A			D40510P	A02			YC059-YC064
0056	22	PA		25-10	23-42-11	TB0506X	A013	1A			D40510P	A02			YC065-YD157
0062	24	PK		29-3	23-32-21	S00045		5	C	*	D40510P	A20			YL951-YL967, YN231-YN235
0063	24	PK		29-3	23-32-21	S00046		5	C	*	D40510P	B20			YL951-YL967, YN231-YN235
0067	24	PK		10-6	52-71-11	D40170P		26			TB0506X	A016	1A		YL951-YR328
0201	22	PA		36-6	23-42-11	SP00595		9			D40540P	A02			YL951-YR328
0202	22	PA		30-6	23-42-11	SP00593		9			D40540P	A18			YL951-YR328
0203	22	PA		36-6	23-42-11	SP00621		9			D40540P	A16			YL951-YR328
0501	22	PA		31-4	24-11-21	D00636		16			D40540P	A04			YC051-YC052, YC065-YR328
0501	22	PA		30-6	24-11-21	D00636		16			D40540P	A04			YC053-YC055
0501	22	PA		31-3	24-11-21	D00636		16			D40540P	A04			YC056-YC064
0502	22	PA		20-10	24-22-21	D00730		16			D46114P	2			YC051-YC052
0502	22	PA		19-11	24-22-21	D00730		16			D46114P	2			YC053-YR328
0503	22	PA		32-5	24-22-21	D00730		5			D40540P	B04			YC051-YC052
0503	22	PA		31-5	24-22-21	D00730		5			D40540P	B04			YC053-YC055
0503	22	PA		32-2	24-22-21	D00730		5			D40540P	B04			YC056-YR328
0504	22	PA		6-3	24-22-21	D00730		15			TB0506Y	B011	1A		YC051-YC052
0504	22	PA		5-5	24-22-21	D00730		15			TB0506Y	B011	1A		YC053-YC058
0504	22	PA		6-2	24-22-21	D00730		15			TB0506Y	B011	1A		YC059-YC064
0504	22	PA		6-4	24-22-21	D00730		15			TB0506Y	B011	1A		YC065-YR328

WIRE LIST

D280A108

91-21-11

Section W2210

Page 22

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice		
W2218	286A2218				P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)											
0505	22	PA		28-11	24-22-21	TB0506Y		B011	1A		D40540P	A05			YC051-YC052, YC059-YC064	
0505	22	PA		28-3	24-22-21	TB0506Y		B011	1A		D40540P	A05			YC053-YC055	
0505	22	PA		29-0	24-22-21	TB0506Y		B011	1A		D40540P	A05			YC056-YC058, YC065-YR328	
0506	22	PA		4-3	24-22-21	D10596		29			TB0506Y	B011	1A		YC051-YC052	
0506	22	PA		4-0	24-22-21	D10596		29			TB0506Y	B011	1A		YC053-YC058	
0506	22	PA		4-6	24-22-21	D10596		29			TB0506Y	B011	1A		YC059-YC064	
0506	22	PA		4-8	24-22-21	D10596		29			TB0506Y	B011	1A		YC065-YR328	
0507	22	PA		6-8	24-28-11	D10596		43			D40536P	3			YC051-YC052, YC059-YR328	
0507	22	PA		6-5	24-28-11	D10596		43			D40536P	3			YC053-YC058	
0508	22	PA		6-8	24-28-11	D10596		38			D40536P	11			YC051-YC052, YC059-YR328	
0508	22	PA		6-5	24-28-11	D10596		38			D40536P	11			YC053-YC058	
0509	22	PA		19-5	24-28-11	D10596		41			D46114P	3			YC051-YC052	
0509	22	PA		18-6	24-28-11	D10596		41			D46114P	3			YC053-YC058	
0509	22	PA		18-9	24-28-11	D10596		41			D46114P	3			YC059-YR328	
0510	22	PA		19-5	24-28-11	D10596		55			D46114P	4			YC051-YC052	
0510	22	PA		18-6	24-28-11	D10596		55			D46114P	4			YC053-YC058	
0510	22	PA		18-9	24-28-11	D10596		55			D46114P	4			YC059-YR328	
0512	20	PA		2-3	24-28-11	D10596		5			GD00505	DC..	1A		YC051-YC052	
0512	20	PA		2-1	24-28-11	D10596		5			GD00515	DC..	1A		YC053-YC058	
0512	20	PA		2-4	24-28-11	D10596		5			GD00515	DC..	1A		YC059-YR328	
0513	20	PA		2-3	24-28-11	D10596		8			GD00505	ST..	1A		YC051-YC052	
0513	20	PA		2-1	24-28-11	D10596		8			GD00515	ST..	1A		YC053-YC058	
0513	20	PA		2-4	24-28-11	D10596		8			GD00515	ST..	1A		YC059-YR328	
0514	20	PA		2-4	24-28-11	D10596		19			GD00507	AC..	1A		YC051-YC052	
0514	20	PA		2-1	24-28-11	D10596		19			GD00517	AC..	1A		YC053-YC058	
0514	20	PA		2-4	24-28-11	D10596		19			GD00517	AC..	1A		YC059-YR328	
0517	22	CQ		4-7	24-22-11	D10596		28			TB0505Y	A003	1A		YC051-YC052, YC059-YR328	
0517	22	CQ		4-1	24-22-11	D10596		28			TB0505Y	A003	1A		YC053-YC058	
0518	20	PA		31-4	27-61-11	D00630		11			D40540P	A03			YC051-YC052	
0518	20	PA		30-5	27-61-11	D00630		11			D40540P	A03			YC053-YC055	
0518	20	PA		31-2	27-61-11	D00630		11			D40540P	A03			YC056-YC058	
0518	20	PA		31-1	27-61-11	D00630		11			D40540P	A03			YC059-YR328	
0519	20	PA		31-4	27-61-11	D00630		3			D40540P	B03			YC051-YC052	
0519	20	PA		30-5	27-61-11	D00630		3			D40540P	B03			YC053-YC055	

WIRE LIST

D280A108

91-21-11

Section W2210

Page 23

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2218		286A2218			P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)											
0519		20		PA		31-2	27-61-11	D00630			3	D40540P		B03		YC056-YC058
0519		20		PA		31-1	27-61-11	D00630			3	D40540P		B03		YC059-YR328
0520		20		PA		31-3	27-61-11	D00624			31	D40540P		A07		YC051-YC052
0520		20		PA		30-4	27-61-11	D00624			31	D40540P		A07		YC053-YC055
0520		20		PA		31-2	27-61-11	D00624			31	D40540P		A07		YC056-YC058
0520		20		PA		31-0	27-61-11	D00624			31	D40540P		A07		YC059-YR328
0521		20		PA		31-3	27-61-11	D00624			19	D40540P		B07		YC051-YC052
0521		20		PA		30-4	27-61-11	D00624			19	D40540P		B07		YC053-YC055
0521		20		PA		31-2	27-61-11	D00624			19	D40540P		B07		YC056-YC058
0521		20		PA		31-0	27-61-11	D00624			19	D40540P		B07		YC059-YR328
0522		20		PA		2-4	24-28-11	D10596			46	GD00503	DC..	1A		YC051-YC052
0522		20		PA		2-5	24-28-11	D10596			46	GD00503	DC..	1A		YC053-YR328
0523		20		PA		1-11	27-81-11	D00650			37	GD00509	DC..	1A		YC051-YC052
0523		20		PA		2-0	27-81-11	D00650			37	GD00509	DC..	1A		YC053-YR328
0524		24		PK		27-11	27-81-11	D00650			16	D40510P		A03		YC051-YC052
0524		24		PK		27-1	27-81-11	D00650			16	D40510P		A03		YC053-YC058
0524		24		PK		27-0	27-81-11	D00650			16	D40510P		A03		YC059-YR328
0525		24		PK		27-11	27-81-11	D00650			15	D40510P		B03		YC051-YC052
0525		24		PK		27-1	27-81-11	D00650			15	D40510P		B03		YC053-YC058
0525		24		PK		27-0	27-81-11	D00650			15	D40510P		B03		YC059-YR328
0526		24		PK		27-11	27-81-11	D00650			17	D40510P		A04		YC051-YC052
0526		24		PK		27-1	27-81-11	D00650			17	D40510P		A04		YC053-YC058
0526		24		PK		27-0	27-81-11	D00650			17	D40510P		A04		YC059-YR328
0527		24		PK		27-11	27-81-11	D00650			18	D40510P		B04		YC051-YC052
0527		24		PK		27-1	27-81-11	D00650			18	D40510P		B04		YC053-YC058
0527		24		PK		27-0	27-81-11	D00650			18	D40510P		B04		YC059-YR328
0528		24		PK		27-11	27-81-12	D00650			5	D40510P		A05		YC051-YC052
0528		24		PK		27-1	27-81-12	D00650			5	D40510P		A05		YC053-YC058
0528		24		PK		27-0	27-81-12	D00650			5	D40510P		A05		YC059-YR328
0529		24		PK		27-11	27-81-12	D00650			4	D40510P		B05		YC051-YC052
0529		24		PK		27-1	27-81-12	D00650			4	D40510P		B05		YC053-YC058
0529		24		PK		27-0	27-81-12	D00650			4	D40510P		B05		YC059-YR328
0530		24		PK		27-11	27-81-12	D00650			3	D40510P		A06		YC051-YC052
0530		24		PK		27-1	27-81-12	D00650			3	D40510P		A06		YC053-YC058
0530		24		PK		27-0	27-81-12	D00650			3	D40510P		A06		YC059-YR328
0531		24		PK		27-11	27-81-12	D00650			8	D40510P		B06		YC051-YC052
0531		24		PK		27-1	27-81-12	D00650			8	D40510P		B06		YC053-YC058
0531		24		PK		27-0	27-81-12	D00650			8	D40510P		B06		YC059-YR328
0532		24		PK		27-11	27-81-12	D00650			7	D40510P		A07		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W2210

Page 24

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2218	286A2218			P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)											
0532	24		PK		27-1	27-81-12	D00650			7	D40510P	A07			YC053-YC058
0532	24		PK		27-0	27-81-12	D00650			7	D40510P	A07			YC059-YR328
0533	24		PK		27-11	27-81-12	D00650			6	D40510P	B07			YC051-YC052
0533	24		PK		27-1	27-81-12	D00650			6	D40510P	B07			YC053-YC058
0533	24		PK		27-0	27-81-12	D00650			6	D40510P	B07			YC059-YR328
0534	24		PK		27-11	27-81-12	D00650			11	D40510P	A08			YC051-YC052
0534	24		PK		27-1	27-81-12	D00650			11	D40510P	A08			YC053-YC058
0534	24		PK		27-0	27-81-12	D00650			11	D40510P	A08			YC059-YR328
0535	24		PK		27-11	27-81-12	D00650			10	D40510P	B08			YC051-YC052
0535	24		PK		27-1	27-81-12	D00650			10	D40510P	B08			YC053-YC058
0535	24		PK		27-0	27-81-12	D00650			10	D40510P	B08			YC059-YR328
0536	24		PK		27-11	27-81-12	D00650			9	D40510P	A09			YC051-YC052
0536	24		PK		27-1	27-81-12	D00650			9	D40510P	A09			YC053-YC058
0536	24		PK		27-0	27-81-12	D00650			9	D40510P	A09			YC059-YR328
0537	24		PK		27-11	27-81-12	D00650			14	D40510P	B09			YC051-YC052
0537	24		PK		27-1	27-81-12	D00650			14	D40510P	B09			YC053-YC058
0537	24		PK		27-0	27-81-12	D00650			14	D40510P	B09			YC059-YR328
0538	24		PK		27-11	27-81-12	D00650			13	D40510P	A10			YC051-YC052
0538	24		PK		27-1	27-81-12	D00650			13	D40510P	A10			YC053-YC058
0538	24		PK		27-0	27-81-12	D00650			13	D40510P	A10			YC059-YR328
0539	24		PK		27-11	27-81-12	D00650			12	D40510P	B10			YC051-YC052
0539	24		PK		27-1	27-81-12	D00650			12	D40510P	B10			YC053-YC058
0539	24		PK		27-0	27-81-12	D00650			12	D40510P	B10			YC059-YR328
0540	24		PK		27-11	27-81-21	D00650			22	D40510P	A11			YC051-YC052
0540	24		PK		27-1	27-81-21	D00650			22	D40510P	A11			YC053-YC058
0540	24		PK		27-0	27-81-21	D00650			22	D40510P	A11			YC059-YR328
0541	24		PK		27-11	27-81-21	D00650			19	D40510P	B11			YC051-YC052
0541	24		PK		27-1	27-81-21	D00650			19	D40510P	B11			YC053-YC058
0541	24		PK		27-0	27-81-21	D00650			19	D40510P	B11			YC059-YR328
0542	24		PK		27-11	27-81-21	D00650			20	D40510P	A12			YC051-YC052
0542	24		PK		27-1	27-81-21	D00650			20	D40510P	A12			YC053-YC058
0542	24		PK		27-0	27-81-21	D00650			20	D40510P	A12			YC059-YR328
0543	24		PK		27-11	27-81-21	D00650			21	D40510P	B12			YC051-YC052
0543	24		PK		27-1	27-81-21	D00650			21	D40510P	B12			YC053-YC058
0543	24		PK		27-0	27-81-21	D00650			21	D40510P	B12			YC059-YR328
0544	24		PK		27-11	27-81-22	D00650			23	D40510P	A13			YC051-YC052
0544	24		PK		27-1	27-81-22	D00650			23	D40510P	A13			YC053-YC058
0544	24		PK		27-0	27-81-22	D00650			23	D40510P	A13			YC059-YR328
0545	24		PK		27-11	27-81-22	D00650			24	D40510P	B13			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W2210

Page 25

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2218		286A2218			P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)											
0545		24		PK		27-1	27-81-22	D00650		24		D40510P		B13		YC053-YC058
0545		24		PK		27-0	27-81-22	D00650		24		D40510P		B13		YC059-YR328
0546		24		PK		27-11	27-81-22	D00650		25		D40510P		A14		YC051-YC052
0546		24		PK		27-1	27-81-22	D00650		25		D40510P		A14		YC053-YC058
0546		24		PK		27-0	27-81-22	D00650		25		D40510P		A14		YC059-YR328
0547		24		PK		27-11	27-81-22	D00650		26		D40510P		B14		YC051-YC052
0547		24		PK		27-1	27-81-22	D00650		26		D40510P		B14		YC053-YC058
0547		24		PK		27-0	27-81-22	D00650		26		D40510P		B14		YC059-YR328
0548		24		PK		27-11	27-81-22	D00650		27		D40510P		A15		YC051-YC052
0548		24		PK		27-1	27-81-22	D00650		27		D40510P		A15		YC053-YC058
0548		24		PK		27-0	27-81-22	D00650		27		D40510P		A15		YC059-YR328
0549		24		PK		27-11	27-81-22	D00650		28		D40510P		B15		YC051-YC052
0549		24		PK		27-1	27-81-22	D00650		28		D40510P		B15		YC053-YC058
0549		24		PK		27-0	27-81-22	D00650		28		D40510P		B15		YC059-YR328
0550		24		PK		27-11	27-81-22	D00650		29		D40510P		A16		YC051-YC052
0550		24		PK		27-1	27-81-22	D00650		29		D40510P		A16		YC053-YC058
0550		24		PK		27-0	27-81-22	D00650		29		D40510P		A16		YC059-YR328
0551		24		PK		27-11	27-81-22	D00650		30		D40510P		B16		YC051-YC052
0551		24		PK		27-1	27-81-22	D00650		30		D40510P		B16		YC053-YC058
0551		24		PK		27-0	27-81-22	D00650		30		D40510P		B16		YC059-YR328
0552		24		PK		27-11	27-81-22	D00650		31		D40510P		A17		YC051-YC052
0552		24		PK		27-1	27-81-22	D00650		31		D40510P		A17		YC053-YC058
0552		24		PK		27-0	27-81-22	D00650		31		D40510P		A17		YC059-YR328
0553		24		PK		27-11	27-81-22	D00650		32		D40510P		B17		YC051-YC052
0553		24		PK		27-1	27-81-22	D00650		32		D40510P		B17		YC053-YC058
0553		24		PK		27-0	27-81-22	D00650		32		D40510P		B17		YC059-YR328
0554		24		PK		27-11	27-81-22	D00650		33		D40510P		A18		YC051-YC052
0554		24		PK		27-1	27-81-22	D00650		33		D40510P		A18		YC053-YC058
0554		24		PK		27-0	27-81-22	D00650		33		D40510P		A18		YC059-YR328
0555		24		PK		27-11	27-81-22	D00650		34		D40510P		B18		YC051-YC052
0555		24		PK		27-1	27-81-22	D00650		34		D40510P		B18		YC053-YC058
0555		24		PK		27-0	27-81-22	D00650		34		D40510P		B18		YC059-YR328
0556		20		PA		1-11	27-81-11	D00650		38		GD00509	ST..	1A		YC051-YC052
0556		20		PA		2-0	27-81-11	D00650		38		GD00509	ST..	1A		YC053-YR328
0557		20		PA		2-4	24-28-11	D10596		17		GD00503	DC..	1A		YC051-YC052
0557		20		PA		2-5	24-28-11	D10596		17		GD00503	DC..	1A		YC053-YR328
0558		20		PA		2-4	24-28-11	D10596		16		GD00503	DC..	1A		YC051-YC052
0558		20		PA		2-5	24-28-11	D10596		16		GD00503	DC..	1A		YC053-YR328
0601		24		PK		19-7	32-64-12	L01001		2	B	D46114P		11		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W2210

Page 26

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To					
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W2218	286A2218				P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)											
0601	24		PK		19-0	32-64-12	L01001		2	B		D46114P	11			YC053-YC058
0601	24		PK		18-11	32-64-12	L01001		2	B		D46114P	11			YC059-YR328
0602	24		PK		19-7	32-64-12	L00481		2	B		D46114P	12			YC051-YC052
0602	24		PK		18-11	32-64-12	L00481		2	B		D46114P	12			YC053-YC058
0602	24		PK		18-10	32-64-12	L00481		2	B		D46114P	12			YC059-YR328
0603	24		PK		19-6	32-64-12	L00482		2	B		D46114P	13			YC051-YC052
0603	24		PK		18-9	32-64-12	L00482		2	B		D46114P	13			YC053-YC058
0603	24		PK		18-8	32-64-12	L00482		2	B		D46114P	13			YC059-YR328
1001	20		X1	AA	31-3	21-31-23	D10726		31			D40542P	A04			YC051-YC052
1001	20		X1	AA	30-5	21-31-23	D10726		31			D40542P	A04			YC053-YC055
1001	20		X1	AA	30-3	21-31-23	D10726		31			D40542P	A04			YC056-YR328
1001Z				AA	0-0	21-31-23	D10726				AA	D40542P	PERG	1F		ALL
1002	20		X1	AB	31-3	21-31-23	D10726		19			D40542P	B04			YC051-YC052
1002	20		X1	AB	30-5	21-31-23	D10726		19			D40542P	B04			YC053-YC055
1002	20		X1	AB	30-3	21-31-23	D10726		19			D40542P	B04			YC056-YD157
1002Z				AB	0-0	21-31-23	D10726				AA	D40542P	PERG	1F		YC051-YD157
1004	20		X1	AB	24-3	21-31-23	D10726		19			D40064P	B05			YD158-YR328
1004Z				AB	0-0	21-31-23	D10726				AA	D40064P	PERG	1F		YD158-YR328
2001B	24		Y2	GA	31-3	21-31-23	D10726		29			D40542P	B05			YC051-YC052
2001B	24		Y2	GA	30-5	21-31-23	D10726		29			D40542P	B05			YC053-YC055
2001B	24		Y2	GA	30-3	21-31-23	D10726		29			D40542P	B05			YC056-YD157
2001R	24		Y2	GA	0-0	21-31-23	D10726		28			D40542P	A05			YC051-YD157
2001Z				GA	0-0	21-31-23	D10726				AA	D40542P	PERG	1F		YC051-YD157
2002B	24		Y2	GB	31-3	21-31-23	D10726		17			D40542P	B06			YC051-YC052
2002B	24		Y2	GB	30-5	21-31-23	D10726		17			D40542P	B06			YC053-YC055
2002B	24		Y2	GB	30-3	21-31-23	D10726		17			D40542P	B06			YC056-YD157
2002R	24		Y2	GB	0-0	21-31-23	D10726		16			D40542P	A06			YC051-YD157
2002Z				GB	0-0	21-31-23	D10726				AA	D40542P	PERG	1F		YC051-YD157
2003B	24		Y2	GC	30-8	30-41-12	D00644		4			D41440P	B03			YC051-YC052
2003B	24		Y2	GC	29-9	30-41-12	D00644		4			D41440P	B03			YC053-YC055
2003B	24		Y2	GC	29-6	30-41-12	D00644		4			D41440P	B03			YC056-YC058
2003B	24		Y2	GC	29-8	30-41-12	D00644		4			D41440P	B03			YC059-YR328
2003R	24		Y2	GC	0-0	30-41-12	D00644		5			D41440P	A03			ALL
2003Z				GC	0-0	30-41-12	GD00506		ST..	1A		D41440P	PERG	1F		ALL
2101B	24		Y2	GA	24-3	21-31-23	D10726		29			D40064P	B03			YD158-YR328
2101R	24		Y2	GA	0-0	21-31-23	D10726		28			D40064P	A03			YD158-YR328
2101Z				GA	0-0	21-31-23	D10726				AA	D40064P	PERG	1F		YD158-YR328
2102B	24		Y2	GB	24-3	21-31-23	D10726		17			D40064P	B06			YD158-YR328
2102R	24		Y2	GB	0-0	21-31-23	D10726		16			D40064P	A06			YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W2210

Page 27

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice
W2218	286A2218			P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)											
2102Z				GB	0-0	21-31-23	D10726			AA	D40064P	PERG	1F	YD158-YR328	
2201B	22	PB	KA	KA	31-0	24-28-11	D00652	29			D40540P	B20		YC051-YC052, YC059-YR328	
2201B	22	PB	KA	KA	30-2	24-28-11	D00652	29			D40540P	B20		YC053-YC055	
2201B	22	PB	KA	KA	30-11	24-28-11	D00652	29			D40540P	B20		YC056-YC058	
2201R	22	PB	KA	KA	0-0	24-28-11	D00652	47			D40540P	A20		ALL	
2202B	22	PB	KB	KB	31-0	24-28-41	D00652	13			D40540P	B08		YC051-YC052, YC059-YR328	
2202B	22	PB	KB	KB	30-2	24-28-41	D00652	13			D40540P	B08		YC053-YC055	
2202B	22	PB	KB	KB	30-11	24-28-41	D00652	13			D40540P	B08		YC056-YC058	
2202R	22	PB	KB	KB	0-0	24-28-41	D00652	12			D40540P	A08		ALL	
2205B	22	PB	KE	KE	32-5	24-41-11	D00634	24			D40540P	B09		YC051-YC052	
2205B	22	PB	KE	KE	31-5	24-41-11	D00634	24			D40540P	B09		YC053-YC055	
2205B	22	PB	KE	KE	32-3	24-41-11	D00634	24			D40540P	B09		YC056-YR328	
2205R	22	PB	KE	KE	0-0	24-41-11	D00634	11			D40540P	A09		ALL	
2601B	22	PB	SA	SA	19-8	30-21-21	D00648	12			D46114P	9		YC051-YC052	
2601B	22	PB	SA	SA	18-10	30-21-21	D00648	12			D46114P	9		YC053-YR328	
2601R	22	PB	SA	SA	0-0	30-21-21	D00648	14			D46114P	8		ALL	
3001B	24	PM	WA	WA	35-3	21-61-13	D41826P	B04			D03998	11		YC051-YC052	
3001B	24	PM	WA	WA	34-6	21-61-13	D41826P	B04			D03998	11		YC053-YC055	
3001B	24	PM	WA	WA	34-5	21-61-13	D41826P	B04			D03998	11		YC056-YL999, YR301-YR328	
3001R	24	PM	WA	WA	0-0	21-61-13	D41826P	B03			D03998	10		YC051-YL999, YR301-YR328	
3001Y	24	PM	WA	WA	0-0	21-61-13	D41826P	B02			D03998	9		YC051-YL999, YR301-YR328	
3002B	24	PM	WB	WB	35-3	21-61-13	D41826P	B07			D03998	5		YC051-YC052	
3002B	24	PM	WB	WB	34-6	21-61-13	D41826P	B07			D03998	5		YC053-YC055	
3002B	24	PM	WB	WB	34-5	21-61-13	D41826P	B07			D03998	5		YC056-YL999, YR301-YR328	
3002R	24	PM	WB	WB	0-0	21-61-13	D41826P	B08			D03998	6		YC051-YL999, YR301-YR328	
3002Y	24	PM	WB	WB	0-0	21-61-13	D41826P	B06			D03998	4		YC051-YL999, YR301-YR328	
3201B	22	X3	YA	YA	32-5	24-22-21	D00730	14			D40540P	A06		YC051-YC052	
3201B	22	X3	YA	YA	31-5	24-22-21	D00730	14			D40540P	A06		YC053-YC055	
3201B	22	X3	YA	YA	32-2	24-22-21	D00730	14			D40540P	A06		YC056-YR328	
3201R	22	X3	YA	YA	0-0	24-22-21	D00730	4			D40540P	B05		ALL	
3201Y	22	X3	YA	YA	0-0	24-22-21	D00730	13			D40540P	B06		ALL	

WIRE LIST

D280A108

91-21-11

Section W2210

Page 28

Nov 12/2012



WIRE LIST
D280A108

91-21-11
Section W2210
Page 29
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W2218	286A2218	P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)													
5511	24	PK	31-3	21-31-23	D10726	9			D40542P	B16			YC051-YC052		
5511	24	PK	30-5	21-31-23	D10726	9			D40542P	B16			YC053-YC055		
5511	24	PK	30-3	21-31-23	D10726	9			D40542P	B16			YC056-YD157		
5512	24	PK	7-8	21-31-25	D10726	12			D40536P	17			YC051-YC052, YC059-YC064		
5512	24	PK	7-6	21-31-25	D10726	12			D40536P	17			YC053-YC055		
5512	24	PK	7-7	21-31-25	D10726	12			D40536P	17			YC056-YC058, YC065-YR328		
5513	24	PK	30-4	21-51-24	D00680	3			D40542P	B08			YC051-YC052		
5513	24	PK	29-8	21-51-24	D00680	3			D40542P	B08			YC053-YC055		
5513	24	PK	29-5	21-51-24	D00680	3			D40542P	B08			YC056-YC058		
5513	24	PK	29-6	21-51-24	D00680	3			D40542P	B08			YC059-YR328		
5514	24	PK	4-3	21-51-22	D00680	1			TB0504Y	B011	1A		YC051-YC058		
5514	24	PK	4-6	21-51-22	D00680	1			TB0504Y	B011	1A		YC059-YC064		
5514	24	PK	4-10	21-51-22	D00680	1			TB0504Y	B011	1A		YC065-YL999, YR301-YR328		
5514	24	PK	4-10	21-61-22	D00680	12			TB0504Y	B011	1A		YN231-YN501		
5515	24	PK	35-5	21-51-22	D00680	55			D41826P	A02			YC051-YC052		
5515	24	PK	34-10	21-51-22	D00680	55			D41826P	A02			YC053-YC055		
5515	24	PK	34-9	21-51-22	D00680	55			D41826P	A02			YC056-YL999, YR301-YR328		
5515	24	PK	2-0	21-61-22	D00680	28			D00620	10			YN231-YN501		
5516	20	PA	2-9	21-51-22	D00680	12			GD00506	DC..	1A		YC051-YC052		
5516	20	PA	2-8	21-51-22	D00680	12			GD00506	DC..	1A		YC053-YC058		
5516	20	PA	2-6	21-51-22	D00680	12			GD00506	DC..	1A		YC059-YL999, YR301-YR328		
5516	24	PK	2-0	21-61-22	D00680	26			D00620	6			YN231-YN501		
5517	24	PK	33-2	21-51-22	D41826P	A01			TB0504Y	B011	1A		YC051-YC052		
5517	24	PK	32-6	21-51-22	D41826P	A01			TB0504Y	B011	1A		YC053-YC055		
5517	24	PK	32-5	21-51-22	D41826P	A01			TB0504Y	B011	1A		YC056-YC058, YC065-YL999, YR301-YR328		
5517	24	PK	32-3	21-51-22	D41826P	A01			TB0504Y	B011	1A		YC059-YC064		
5517	24	PK	4-0	21-61-22	D40536P	24			TB0504Y	B011	1A		YN231-YN501		
5518	24	PK	28-1	21-51-22	TB0504Y	B011	1A		D40542P	A09			YC051-YC052		
5518	24	PK	27-4	21-51-22	TB0504Y	B011	1A		D40542P	A09			YC053-YC055		
5518	24	PK	27-1	21-51-22	TB0504Y	B011	1A		D40542P	A09			YC056-YC058, YC065-YL999, YR301-YR328		

WIRE LIST

D280A108

91-21-11

Section W2210

Page 30

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2218	286A2218				P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)										
5518	24		PK		27-0	21-51-22	TB0504Y	B011	1A		D40542P	A09			YC059-YC064
5518	24		PK		27-1	21-61-22	TB0504Y	B011	1A		D40542P	A09			YN231-YN501
5519	24		PK		30-4	21-51-22	D00680		26		D40542P	B09			YC051-YC052
5519	24		PK		29-8	21-51-22	D00680		26		D40542P	B09			YC053-YC055
5519	24		PK		29-5	21-51-22	D00680		26		D40542P	B09			YC056-YC058
5519	24		PK		29-6	21-51-22	D00680		26		D40542P	B09			YC059-YL999, YR301-YR328
5519	24		PK		29-4	21-61-22	D00620		3		D40542P	B09			YN231-YN501
5520	24		PK		28-3	21-61-13	TB0506Y	A009	1A		D40542P	A10			YC051-YC052
5520	24		PK		27-6	21-61-13	TB0506Y	A009	1A		D40542P	A10			YC053-YC055
5520	24		PK		27-3	21-61-13	TB0506Y	A009	1A		D40542P	A10			YC056-YC058
5520	24		PK		27-2	21-61-13	TB0506Y	A009	1A		D40542P	A10			YC059-YL999, YR301-YR328
5520	24		PK		29-4	21-61-22	D00620		5		D40542P	A10			YN231-YN501
5521	24		PK		4-4	21-61-13	D00680		32		TB0506Y	A009	1A		YC051-YC052
5521	24		PK		4-5	21-61-13	D00680		32		TB0506Y	A009	1A		YC053-YC058
5521	24		PK		4-8	21-61-13	D00680		32		TB0506Y	A009	1A		YC059-YC064
5521	24		PK		4-11	21-61-13	D00680		32		TB0506Y	A009	1A		YC065-YL999, YR301-YR328
5521	24		PK		29-4	21-61-22	D00620		1		D40542P	B10			YN231-YN501
5522	24		PK		30-4	21-61-13	D00680		40		D40542P	A11			YC051-YC052
5522	24		PK		29-8	21-61-13	D00680		40		D40542P	A11			YC053-YC055
5522	24		PK		29-5	21-61-13	D00680		40		D40542P	A11			YC056-YC058
5522	24		PK		29-6	21-61-13	D00680		40		D40542P	A11			YC059-YL999, YR301-YR328
5522	24		PK		29-4	21-61-22	D00620		2		D40542P	A11			YN231-YN501
5523	24		PK		29-4	21-61-22	D00620		4		D40542P	B11			YN231-YN501
5524	24		PK		29-5	21-61-22	D00656		16		D40542P	A12			YN231-YN501
5525	24		PK		4-9	21-61-22	D00656		14		TB0504Y	A011	1A		YN231-YN501
5526	24		PK		4-10	21-61-22	D00680		32		TB0504Y	A011	1A		YN231-YN501
5527	24		PK		27-1	21-61-22	TB0504Y	A011	1A		D40542P	B12			YN231-YN501
5528	24		PK		27-2	21-61-22	TB0504Y	B007	1A		D40542P	A17			YN231-YN501
5530	20		PA		6-5	30-41-12	D00644		52		D40536P		25		YC051-YC052, YC059-YR328
5530	20		PA		6-3	30-41-12	D00644		52		D40536P		25		YC053-YC058
5531	20		PA		6-5	30-41-12	D00644		49		D40536P		12		YC051-YC052, YC059-YR328
5531	20		PA		6-3	30-41-12	D00644		49		D40536P		12		YC053-YC058
5532	24		PK		5-0	30-41-12	D00644		50		D40538P		11		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W2210

Page 31

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2218	286A2218			P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)											
5532	24	PK		5-1	30-41-12	D00644		50			D40538P	11			YC053-YC058
5532	24	PK		5-3	30-41-12	D00644		50			D40538P	11			YC059-YR328
5533	24	PK		5-0	30-41-12	D00644		51			D40538P	12			YC051-YC052
5533	24	PK		5-1	30-41-12	D00644		51			D40538P	12			YC053-YC058
5533	24	PK		5-3	30-41-12	D00644		51			D40538P	12			YC059-YR328
5534	24	PK		30-8	30-41-12	D00644		47			D41440P	A01			YC051-YC052
5534	24	PK		29-9	30-41-12	D00644		47			D41440P	A01			YC053-YC055
5534	24	PK		29-6	30-41-12	D00644		47			D41440P	A01			YC056-YC058
5534	24	PK		29-8	30-41-12	D00644		47			D41440P	A01			YC059-YR328
5535	24	PK		30-8	30-41-12	D00644		7			D41440P	B01			YC051-YC052
5535	24	PK		29-9	30-41-12	D00644		7			D41440P	B01			YC053-YC055
5535	24	PK		29-6	30-41-12	D00644		7			D41440P	B01			YC056-YC058
5535	24	PK		29-8	30-41-12	D00644		7			D41440P	B01			YC059-YR328
5536	24	PK		30-8	30-41-12	D00644		6			D41440P	A02			YC051-YC052
5536	24	PK		29-9	30-41-12	D00644		6			D41440P	A02			YC053-YC055
5536	24	PK		29-6	30-41-12	D00644		6			D41440P	A02			YC056-YC058
5536	24	PK		29-8	30-41-12	D00644		6			D41440P	A02			YC059-YR328
5537	24	PK		30-8	30-41-12	D00644		8			D41440P	B02			YC051-YC052
5537	24	PK		29-9	30-41-12	D00644		8			D41440P	B02			YC053-YC055
5537	24	PK		29-6	30-41-12	D00644		8			D41440P	B02			YC056-YC058
5537	24	PK		29-8	30-41-12	D00644		8			D41440P	B02			YC059-YR328
5538	24	PK		30-8	30-41-12	D00644		9			D41440P	A05			YC051-YC052
5538	24	PK		29-9	30-41-12	D00644		9			D41440P	A05			YC053-YC055
5538	24	PK		29-6	30-41-12	D00644		9			D41440P	A05			YC056-YC058
5538	24	PK		29-8	30-41-12	D00644		9			D41440P	A05			YC059-YR328
5539	24	PK		30-8	30-41-12	D00644		1			D41440P	B05			YC051-YC052
5539	24	PK		29-9	30-41-12	D00644		1			D41440P	B05			YC053-YC055
5539	24	PK		29-6	30-41-12	D00644		1			D41440P	B05			YC056-YC058
5539	24	PK		29-8	30-41-12	D00644		1			D41440P	B05			YC059-YR328
5540	24	PK		30-8	30-41-12	D00644		2			D41440P	A04			YC051-YC052
5540	24	PK		29-9	30-41-12	D00644		2			D41440P	A04			YC053-YC055
5540	24	PK		29-6	30-41-12	D00644		2			D41440P	A04			YC056-YC058
5540	24	PK		29-8	30-41-12	D00644		2			D41440P	A04			YC059-YR328
5541	24	PK		30-8	30-41-12	D00644		48			D41440P	B04			YC051-YC052
5541	24	PK		29-9	30-41-12	D00644		48			D41440P	B04			YC053-YC055
5541	24	PK		29-6	30-41-12	D00644		48			D41440P	B04			YC056-YC058
5541	24	PK		29-8	30-41-12	D00644		48			D41440P	B04			YC059-YR328
5542	24	PK		19-6	36-11-11	D00680		14			D46114P	14			YC051-YC052
5542	24	PK		18-10	36-11-11	D00680		14			D46114P	14			YC053-YC058

WIRE LIST

D280A108

91-21-11

Section W2210

Page 32

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity			
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice	
W2218	286A2218				P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)											
5542	24		PK		18-11	36-11-11	D00680			14		D46114P	14			YC059-YR328
5543	24		PK		19-6	36-11-11	D00680			15		D46114P	15			YC051-YC052
5543	24		PK		18-10	36-11-11	D00680			15		D46114P	15			YC053-YC058
5543	24		PK		18-11	36-11-11	D00680			15		D46114P	15			YC059-YR328
5544	24		PK		19-4	36-11-11	D46114P			16		D40542P	A13			YC051-YC055
5544	24		PK		19-1	36-11-11	D46114P			16		D40542P	A13			YC056-YR328
5545	20		PA		2-9	36-11-11	D00680			4		GD00506	DC..	1A		YC051-YC052
5545	20		PA		2-8	36-11-11	D00680			4		GD00506	DC..	1A		YC053-YC058
5545	20		PA		2-6	36-11-11	D00680			4		GD00506	DC..	1A		YC059-YR328
5546	24		PK		30-4	36-11-11	D00680			16		D40542P	B13			YC051-YC052
5546	24		PK		29-8	36-11-11	D00680			16		D40542P	B13			YC053-YC055
5546	24		PK		29-5	36-11-11	D00680			16		D40542P	B13			YC056-YC058
5546	24		PK		29-6	36-11-11	D00680			16		D40542P	B13			YC059-YR328
5547	24		PK		30-4	36-11-11	D00680			19		D40542P	A14			YC051-YC052
5547	24		PK		29-8	36-11-11	D00680			19		D40542P	A14			YC053-YC055
5547	24		PK		29-5	36-11-11	D00680			19		D40542P	A14			YC056-YC058
5547	24		PK		29-6	36-11-11	D00680			19		D40542P	A14			YC059-YR328
5548	24		PK		4-11	36-11-11	D00680			43		TB0506Y	A009	1A		YN231-YN501
5549	24		PK		30-4	36-11-11	D00680			44		D40542P	B14			YC051-YC052
5549	24		PK		29-8	36-11-11	D00680			44		D40542P	B14			YC053-YC055
5549	24		PK		29-5	36-11-11	D00680			44		D40542P	B14			YC056-YC058
5549	24		PK		29-6	36-11-11	D00680			44		D40542P	B14			YC059-YR328
5550	20		PA		3-3	36-21-11	D00096			9		GD00506	AC..	1A		YC051-YC052
5550	20		PA		3-0	36-21-11	D00096			9		GD00506	AC..	1A		YC053-YC058, YC065-YR328
5550	20		PA		3-1	36-21-11	D00096			9		GD00506	AC..	1A		YC059-YC064
5551	24		PK		35-5	21-51-22	D00680			2		D41826P	A03			YC051-YC052
5551	24		PK		34-10	21-51-22	D00680			2		D41826P	A03			YC053-YC055
5551	24		PK		34-9	21-51-22	D00680			2		D41826P	A03			YC056-YL999, YR301-YR328
5552	24		PK		4-2	21-61-13	D03998			7		TB0506Y	A009	1A		YC051-YC052
5552	24		PK		4-1	21-61-13	D03998			7		TB0506Y	A009	1A		YC053-YC058
5552	24		PK		4-4	21-61-13	D03998			7		TB0506Y	A009	1A		YC059-YC064
5552	24		PK		4-6	21-61-13	D03998			7		TB0506Y	A009	1A		YC065-YL999, YR301-YR328
5553	24		PK		30-10	36-21-11	D00096			5		D40542P	A15			YC051-YC052
5553	24		PK		30-0	36-21-11	D00096			5		D40542P	A15			YC053-YC055, YC059-YC064
5553	24		PK		29-9	36-21-11	D00096			5		D40542P	A15			YC056-YC058

WIRE LIST

D280A108

91-21-11

Section W2210

Page 33

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W2218	286A2218				P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)												
5553	24	PK			29-11	36-21-11		D00096		5			D40542P	A15			YC065-YR328
5554	24	PK			28-3	36-21-11		TB0504Y	B001	1A			D40542P	B15			YC051-YC052
5554	24	PK			27-6	36-21-11		TB0504Y	B001	1A			D40542P	B15			YC053-YC055
5554	24	PK			27-3	36-21-11		TB0504Y	B001	1A			D40542P	B15			YC056-YC058, YC065-YR328
5554	24	PK			27-2	36-21-11		TB0504Y	B001	1A			D40542P	B15			YC059-YC064
5555	24	PK			35-5	21-61-13		D41826P	B05				D00680	5			YC051-YC052
5555	24	PK			34-10	21-61-13		D41826P	B05				D00680	5			YC053-YC055
5555	24	PK			34-9	21-61-13		D41826P	B05				D00680	5			YC056-YL999, YR301-YR328
5556	24	PK			35-3	21-61-13		D41826P	B01				D03998	8			YC051-YC052
5556	24	PK			34-6	21-61-13		D41826P	B01				D03998	8			YC053-YC055
5556	24	PK			34-5	21-61-13		D41826P	B01				D03998	8			YC056-YL999, YR301-YR328
5557	24	PK			7-3	36-21-11		D00096		8			D40536P	8			YC051-YC052, YC065-YR328
5557	24	PK			7-1	36-21-11		D00096		8			D40536P	8			YC053-YC058
5557	24	PK			7-4	36-21-11		D00096		8			D40536P	8			YC059-YC064
5558	22	PA			6-5	30-31-11		D00644		33			D40536P	20			YC051-YC052, YC059-YR328
5558	22	PA			6-3	30-31-11		D00644		33			D40536P	20			YC053-YC058
5559	20	PA			6-7	21-61-51		D40536P		21			D00090	2			YC051-YC052
5559	20	PA			6-6	21-61-51		D40536P		21			D00090	2			YC053-YR328
5560	18	PA			9-11	33-14-12		SP00070		S			D40536P	1	18		YC051-YC052
5560	18	PA			9-8	33-14-12		SP00070		S			D40536P	1	18		YC053-YC058, YC065-YR328
5560	18	PA			9-7	33-14-12		SP00070		S			D40536P	1	18		YC059-YC064
5561	18	PA			5-5	33-14-12		SP00072		S			GD00510	AC..	1		YC051-YC058
5561	18	PA			6-0	33-14-12		SP00072		S			GD00510	AC..	1		YC059-YR328
5562	18	PA			8-7	33-14-12		T00060	HV	D			D40536P	29	18		YC051-YC052, YC065-YR328
5562	18	PA			8-6	33-14-12		T00060	HV	D			D40536P	29	18		YC053-YC064
5563	18	PA			4-3	33-14-12		T00060	G	D			GD00510	AC..	1		YC051-YC052
5563	18	PA			4-4	33-14-12		T00060	G	D			GD00510	AC..	1		YC053-YC058, YC065-YR328
5563	18	PA			4-5	33-14-12		T00060	G	D			GD00510	AC..	1		YC059-YC064
5564	18	PA			7-10	33-14-12		T00060	LV	D			TB0262V	A013	1		YC051-YC052, YC059-YC064
5564	18	PA			7-11	33-14-12		T00060	LV	D			TB0262V	A013	1		YC053-YC058

WIRE LIST

D280A108

91-21-11

Section W2210

Page 34

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number		Fam	Description		From		To			Effectivity			
	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip		Term	Type	Splice
W2218	286A2218			P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)										
5564	18	PA		8-4	33-14-12	T00060		LV	D	TB0262V	A013	1		YC065-YR328
5565	20	PA		2-7	21-61-13	D03998		12		GD00506	DC..	1A		YC051-YC052
5565	20	PA		2-4	21-61-13	D03998		12		GD00506	DC..	1A		YC053-YC058
5565	20	PA		2-2	21-61-13	D03998		12		GD00506	DC..	1A		YC059-YL999, YR301-YR328
5566	20	PA		6-7	21-61-15	D40536P		24		D03998		13		YC051-YC052
5566	20	PA		6-5	21-61-15	D40536P		24		D03998		13		YC053-YC058
5566	20	PA		6-6	21-61-15	D40536P		24		D03998		13		YC059-YL999, YR301-YR328
5567	20	PA		2-7	21-61-15	GD00506		DC..	1A	D03998		14		YC051-YC052
5567	20	PA		2-4	21-61-15	GD00506		DC..	1A	D03998		14		YC053-YC058
5567	20	PA		2-2	21-61-15	GD00506		DC..	1A	D03998		14		YC059-YL999, YR301-YR328
5568	22	PA		35-3	21-61-15	D41826P		A09		D03998		15		YC051-YC052
5568	22	PA		34-6	21-61-15	D41826P		A09		D03998		15		YC053-YC055
5568	22	PA		34-5	21-61-15	D41826P		A09		D03998		15		YC056-YL999, YR301-YR328
5569	20	PA		30-2	21-61-15	D40542P		A12		D03998		16		YC051-YC052
5569	20	PA		29-4	21-61-15	D40542P		A12		D03998		16		YC053-YC055
5569	20	PA		29-1	21-61-15	D40542P		A12		D03998		16		YC056-YL999, YR301-YR328
5573	20	PA		2-5	30-41-12	D00644		58		GD00506	ST..	1A		YC051-YC052
5573	20	PA		2-2	30-41-12	D00644		58		GD00506	ST..	1A		YC053-YR328
5574	24	PK		23-9	30-42-11	S00022		23	C	TB0608X	A001	1A		YC051-YC052
5574	24	PK		22-8	30-42-11	S00022		23	C	TB0608X	A001	1A		YC053-YC055
5574	24	PK		22-7	30-42-11	S00022		23	C	TB0608X	A001	1A		YC056-YC058
5574	24	PK		22-10	30-42-11	S00022		23	C	TB0608X	A001	1A		YC059-YR328
5575	18	PA		1-4	30-42-11	S00022		21	C	GD00510	DC..	1		YC051-YC052, YC059-YC064
5575	18	PA		1-3	30-42-11	S00022		21	C	GD00510	DC..	1		YC053-YC055
5575	18	PA		1-2	30-42-11	S00022		21	C	GD00510	DC..	1		YC056-YC058
5575	18	PA		1-5	30-42-11	S00022		21	C	GD00510	DC..	1		YC065-YR328
5576	20	PA		4-11	36-21-11	D00096		6		TB0504Y	B001	1A		YC051-YC052
5576	20	PA		4-9	36-21-11	D00096		6		TB0504Y	B001	1A		YC053-YC058
5576	20	PA		5-3	36-21-11	D00096		6		TB0504Y	B001	1A		YC059-YC064
5576	20	PA		5-5	36-21-11	D00096		6		TB0504Y	B001	1A		YC065-YR328
5577	20	PA		3-11	36-21-11	GD00502		DC..	1A	TB0504Y	B001	1A		YC051-YC052
5577	20	PA		3-11	36-21-11	GD00516		DC..	1A	TB0504Y	B001	1A		YC053-YC064
5577	20	PA		4-2	36-21-11	GD00516		DC..	1A	TB0504Y	B001	1A		YC065-YR328

WIRE LIST

D280A108

91-21-11

Section W2210

Page 35

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2218		286A2218			P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)											
5578		20		PA		2-11	36-21-11	D00096		7		GD00502	ST..	1A		YC051-YC052
5578		20		PA		2-9	36-21-11	D00096		7		GD00516	ST..	1A		YC053-YC058
5578		20		PA		3-0	36-21-11	D00096		7		GD00516	ST..	1A		YC059-YC064
5578		20		PA		2-11	36-21-11	D00096		7		GD00516	ST..	1A		YC065-YR328
5601		18		GA		4-6	33-12-12	D40536P		15	18	D40570P	S	18		YC051-YC052
5601		18		PA		4-4	33-12-12	D40536P		15	18	TB0501V	A029	1		YC053-YC064
5601		18		PA		4-7	33-12-12	D40536P		15	18	TB0501V	A029	1		YC065-YR328
5602		20		GA		3-10	33-12-12	D00650		2		D40570P	Z-			YC051-YC052
5602		20		PA		3-8	33-12-12	D00650		2		TB0501Z	A017	1A		YC053-YC058
5602		20		PA		3-9	33-12-12	D00650		2		TB0501Z	A017	1A		YC059-YC064
5602		20		PA		3-7	33-12-12	D00650		2		TB0501Z	A017	1A		YC065-YR328
5603		20		GA		3-10	33-12-12	D00650		1		D40570P	C-			YC051-YC052
5603		20		PA		3-4	33-12-12	D00650		1		TB0501Z	B005	1A		YC053-YC058, YC065-YR328
5603		20		PA		3-6	33-12-12	D00650		1		TB0501Z	B005	1A		YC059-YC064
5604		20		GA		6-11	33-12-12	L00384		=P	B	D40570P	FF			YC051-YC052
5604		20		PA		6-8	33-12-12	L00384		=P	B	TB0501Z	A017	1A		YC053-YC058
5604		20		PA		7-0	33-12-12	L00384		=P	B	TB0501Z	A017	1A		YC059-YC064
5604		20		PA		7-8	33-12-12	L00384		=P	B	TB0501Z	A017	1A		YC065-YR328
5605		20		GA		7-0	33-12-12	L00384		=G	G	D40570P	EE			YC051-YC052
5605		20		PA		4-0	33-12-12	L00384		=G	G	GD00510	AC..	1		YC053-YC058
5605		20		PA		4-2	33-12-12	L00384		=G	G	GD00510	AC..	1		YC059-YC064
5605		20		PA		1-6	33-12-12	L00384		=G	G	GD00510	AC..	1		YC065-YR328
5606		20		GA		4-3	33-12-12	L00385		=P	B	D40570P	R			YC051-YC052
5606		20		PA		4-2	33-12-12	L00385		=P	B	TB0501Z	A017	1A		YC053-YC058
5606		20		PA		4-3	33-12-12	L00385		=P	B	TB0501Z	A017	1A		YC059-YC064
5606		20		PA		4-0	33-12-12	L00385		=P	B	TB0501Z	A017	1A		YC065-YR328
5607		20		GA		4-3	33-12-12	L00385		=G	G	D40570P	F			YC051-YC052
5607		20		PA		3-10	33-12-12	L00385		=G	G	TB0501Z	B005	1A		YC053-YC058
5607		20		PA		4-0	33-12-12	L00385		=G	G	TB0501Z	B005	1A		YC059-YC064
5607		20		PA		3-9	33-12-12	L00385		=G	G	TB0501Z	B005	1A		YC065-YR328
5608		20		GA		7-3	33-12-12	L00383		=P	B	D40570P	AA			YC051-YC052
5608		20		PA		6-11	33-12-12	L00383		=P	B	TB0501Z	A017	1A		YC053-YC055
5608		20		PA		6-10	33-12-12	L00383		=P	B	TB0501Z	A017	1A		YC056-YC058
5608		20		PA		7-2	33-12-12	L00383		=P	B	TB0501Z	A017	1A		YC059-YC064
5608		20		PA		7-4	33-12-12	L00383		=P	B	TB0501Z	A017	1A		YC065-YR328
5609		20		GA		7-4	33-12-12	L00383		=G	G	D40570P	CC			YC051-YC052
5609		20		PA		1-10	33-12-12	L00383		=G	G	GD00510	AC..	1		YC053-YC055
5609		20		PA		1-9	33-12-12	L00383		=G	G	GD00510	AC..	1		YC056-YC058

WIRE LIST

D280A108

91-21-11

Section W2210

Page 36

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice Effectivity
W2218	286A2218	P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)		
5609	20 PA	1-11 33-12-12	L00383 =G G	GD00510 AC.. 1 YC059-YR328
5610	20 GA	3-7 33-12-12	D03172 1	D40570P M- YC051-YC052
5610	20 PA	3-7 33-12-12	D03172 1	TB0501Z A017 1A YC053-YC058
5610	20 PA	3-8 33-12-12	D03172 1	TB0501Z A017 1A YC059-YC064
5610	20 PA	4-0 33-12-12	D03172 1	TB0501Z A017 1A YC065-YR328
5611	20 GA	3-7 33-12-12	D03172 2	D40570P A- YC051-YC052
5611	20 PA	3-4 33-12-12	D03172 2	TB0502Z B013 1A YC053-YC058
5611	20 PA	3-5 33-12-12	D03172 2	TB0502Z B013 1A YC059-YC064
5611	20 PA	3-7 33-12-12	D03172 2	TB0502Z B013 1A YC065-YR328
5612	20 GA	3-9 33-12-12	GD00508 AC.. 1A YC051-YC052	
5651	18 GA	4-6 33-12-12	D40536P 27 18 YC051-YC052	
5651	18 PA	4-4 33-12-12	D40536P 27 18 YC053-YC064	
5651	18 PA	4-7 33-12-12	D40536P 27 18 YC065-YR328	
5654	20 GA	1-11 33-12-12	TB0506Y A011 1A YC051-YC052	
5654	20 PA	2-6 33-12-12	TB0506Y A011 1A YC053-YC058	
5654	20 PA	2-8 33-12-12	TB0506Y A011 1A YC059-YC064	
5654	20 PA	2-10 33-12-12	TB0506Y A011 1A YC065-YR328	
5655	20 GA	1-8 33-12-12	TB0502Y A019 1A YC051-YC052	
5655	20 PA	3-7 33-12-12	TB0502Y A019 1A YC053-YC058	
5655	20 PA	3-8 33-12-12	TB0502Y A019 1A YC059-YC064	
5655	20 PA	3-6 33-12-12	TB0502Y A019 1A YC065-YD158	
5655	20 PA	3-3 33-12-12	TB0506X A015 1A YL951-YR328	
5656	20 GA	3-8 33-12-12	D00432 3 YC051-YC052	
5656	20 PA	3-8 33-12-12	D00432 3 TB0501Z B017 1A YC053-YC058	
5656	20 PA	3-10 33-12-12	D00432 3 TB0501Z B017 1A YC059-YC064	
5656	20 PA	3-11 33-12-12	D00432 3 TB0501Z B017 1A YC065-YR328	
5657	20 GA	3-8 33-12-12	D00432 4 YC051-YC052	
5657	20 PA	3-5 33-12-12	D00432 4 TB0502Z B013 1A YC053-YC058	
5657	20 PA	3-7 33-12-12	D00432 4 TB0502Z B013 1A YC059-YR328	
5658	20 GA	3-6 33-12-12	D00440 2 YC051-YC052	
5658	20 PA	3-6 33-12-12	D00440 2 TB0501Z B017 1A YC053-YC058	
5658	20 PA	3-8 33-12-12	D00440 2 TB0501Z B017 1A YC059-YC064	
5658	20 PA	3-9 33-12-12	D00440 2 TB0501Z B017 1A YC065-YR328	
5659	20 GA	3-6 33-12-12	D00440 1 YC051-YC052	
5659	20 PA	3-4 33-12-12	D00440 1 TB0502Z B013 1A YC053-YC058	
5659	20 PA	3-5 33-12-12	D00440 1 TB0502Z B013 1A YC059-YR328	
5660	20 GA	3-11 33-12-12	D02171 1 YC051-YC052	
5660	20 PA	3-9 33-12-12	D02171 1 TB0501Z B017 1A YC053-YC058	
5660	20 PA	3-10 33-12-12	D02171 1 TB0501Z B017 1A YC059-YC064	

WIRE LIST

D280A108

91-21-11

Section W2210

Page 37

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2218		286A2218				P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)									
	5660	20	PA		3-8	33-12-12	D02171		1		TB0501Z	B017	1A		YC065-YR328
	5661	20	GA		3-11	33-12-12	D02171		2		D40570P	G-			YC051-YC052
	5661	20	PA		3-5	33-12-12	D02171		2		TB0501Z	B005	1A		YC053-YC058, YC065-YR328
	5661	20	PA		3-7	33-12-12	D02171		2		TB0501Z	B005	1A		YC059-YC064
	5662	20	GA		4-1	33-12-12	D02169		1		D40570P	Y			YC051-YC052
	5662	20	PA		3-10	33-12-12	D02169		1		TB0501Z	B017	1A		YC053-YC064
	5662	20	PA		3-7	33-12-12	D02169		1		TB0501Z	B017	1A		YC065-YR328
	5663	20	GA		4-1	33-12-12	D02169		2		D40570P	E-			YC051-YC052
	5663	20	PA		3-7	33-12-12	D02169		2		TB0501Z	B005	1A		YC053-YC058
	5663	20	PA		3-6	33-12-12	D02169		2		TB0501Z	B005	1A		YC059-YC064
	5663	20	PA		3-4	33-12-12	D02169		2		TB0501Z	B005	1A		YC065-YR328
	5664	20	GA		3-10	33-12-12	D02183		1		D40570P	D			YC051-YC052
	5664	20	PA		3-8	33-12-12	D02183		1		TB0501Z	B017	1A		YC053-YC058
	5664	20	PA		4-0	33-12-12	D02183		1		TB0501Z	B017	1A		YC059-YC064
	5664	20	PA		3-9	33-12-12	D02183		1		TB0501Z	B017	1A		YC065-YR328
	5665	20	GA		3-10	33-12-12	D02183		2		D40570P	F-			YC051-YC052
	5665	20	PA		3-5	33-12-12	D02183		2		TB0501Z	B005	1A		YC053-YC058
	5665	20	PA		3-8	33-12-12	D02183		2		TB0501Z	B005	1A		YC059-YC064
	5665	20	PA		3-6	33-12-12	D02183		2		TB0501Z	B005	1A		YC065-YR328
	5666	20	GA		3-9	33-12-12	GD00508	AC..	1A		D40570P	K			YC051-YC052
	5701	18	GA		4-6	33-12-12	D40572P	A	18		D40536P	14	18		YC051-YC052
	5701	18	PA		4-4	33-12-12	TB0501V	B031	1		D40536P	14	18		YC053-YC064
	5701	18	PA		4-7	33-12-12	TB0501V	B031	1		D40536P	14	18		YC065-YR328
	5702	20	GA		6-6	33-12-12	D00446		3		D40572P	C			YC051-YC052
	5702	20	PA		3-11	33-12-12	D00446		3		TB0507Z	B013	1A		YC053-YC058
	5702	20	PA		3-5	33-12-12	D00446		3		TB0507Z	B013	1A		YC059-YR328
	5703	20	GA		6-6	33-12-12	D00446		4		D40572P	M			YC051-YC052
	5703	20	PA		3-5	33-12-12	D00446		4		GD00519	AC..	1A		YC053-YC058
	5703	20	PA		3-6	33-12-12	D00446		4		GD00519	AC..	1A		YC059-YR328
	5704	20	GA		4-11	33-12-12	D00648		2		D40572P	Y			YC051-YC052
	5704	20	PA		6-7	33-12-12	D00648		2		TB0507Z	B013	1A		YC053-YC055
	5704	20	PA		6-6	33-12-12	D00648		2		TB0507Z	B013	1A		YC056-YC058
	5704	20	PA		5-4	33-12-12	D00648		2		TB0507Z	B013	1A		YC059-YR328
	5705	20	GA		4-11	33-12-12	D00648		1		D40572P	H-			YC051-YC052
	5705	20	PA		2-8	33-12-12	D00648		1		GD00520	AC..	1A		YC053-YC058
	5705	20	PA		2-5	33-12-12	D00648		1		GD00520	AC..	1A		YC059-YR328
	5708	20	GA		6-6	33-12-12	D00722		1		D40572P	U			YC051-YC052
	5708	20	PA		3-10	33-12-12	D00722		1		TB0507Z	B013	1A		YC053-YC058

WIRE LIST

D280A108

91-21-11

Section W2210

Page 38

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2218	286A2218			P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)											
5708	20		PA		3-5	33-12-12	D00722			1	TB0507Z	B013	1A		YC059-YR328
5709	20		GA		6-6	33-12-12	D00722			2	D40572P	N			YC051-YC052
5709	20		PA		3-4	33-12-12	D00722			2	GD00519	AC..	1A		YC053-YC058
5709	20		PA		3-6	33-12-12	D00722			2	GD00519	AC..	1A		YC059-YR328
5710	20		GA		4-8	33-12-12	D10596			26	D40572P	J			YC051-YC052
5710	20		PA		2-1	33-12-12	D10596			26	GD00519	AC..	1A		YC053-YC058
5710	20		PA		2-5	33-12-12	D10596			26	GD00519	AC..	1A		YC059-YR328
5711	20		GA		4-8	33-12-12	D10596			44	D40572P	W			YC051-YC052
5711	20		PA		2-7	33-12-12	D10596			44	TB0507Z	B013	1A		YC053-YC058
5711	20		PA		2-4	33-12-12	D10596			44	TB0507Z	B013	1A		YC059-YR328
5712	20		GA		5-0	33-12-12	D00636			1	D40572P	B			YC051-YC052
5712	20		PA		3-0	33-12-12	D00636			1	TB0507Z	B013	1A		YC053-YC058
5712	20		PA		2-7	33-12-12	D00636			1	TB0507Z	B013	1A		YC059-YC064
5712	20		PA		2-8	33-12-12	D00636			1	TB0507Z	B013	1A		YC065-YR328
5713	20		GA		5-0	33-12-12	D00636			2	D40572P	L			YC051-YC052
5713	20		PA		2-6	33-12-12	D00636			2	GD00519	AC..	1A		YC053-YC058
5713	20		PA		2-8	33-12-12	D00636			2	GD00519	AC..	1A		YC059-YC064
5713	20		PA		2-9	33-12-12	D00636			2	GD00519	AC..	1A		YC065-YR328
5714	20		GA		3-9	33-12-12	GD00508	AC..	1A		D40572P	K			YC051-YC052
5715	20		GA		6-7	33-12-12	D11988			1	D40572P	X			YC051-YC052
5715	20		PA		3-11	33-12-12	D11988			1	TB0507Z	B013	1A		YC053-YC058
5715	20		PA		3-6	33-12-12	D11988			1	TB0507Z	B013	1A		YC059-YR328
5716	20		GA		6-7	33-12-12	D11988			2	D40572P	G-			YC051-YC052
5716	20		PA		3-6	33-12-12	D11988			2	GD00519	AC..	1A		YC053-YC064
5716	20		PA		3-7	33-12-12	D11988			2	GD00519	AC..	1A		YC065-YR328
5717	20		PA		3-8	33-12-12	D02889			13	D40570P	W			YC051-YC052
5717	20		PA		3-6	33-12-12	D02889			13	TB0501Z	B017	1A		YC053-YC058
5717	20		PA		3-7	33-12-12	D02889			13	TB0501Z	B017	1A		YC059-YC064
5717	20		PA		3-4	33-12-12	D02889			13	TB0501Z	B017	1A		YC065-YR328
5718	20		PA		3-8	33-12-12	D02889			14	D40570P	J			YC051-YC052
5718	20		PA		3-3	33-12-12	D02889			14	TB0502Z	B013	1A		YC053-YC058
5718	20		PA		3-4	33-12-12	D02889			14	TB0502Z	B013	1A		YC059-YC064
5718	20		PA		3-8	33-12-12	D02889			14	TB0502Z	B013	1A		YC065-YR328
5733	20		PA		3-6	33-12-12	TB0502Z	B013	1A		GD00508	AC..	1A		YC053-YC058
5733	20		PA		3-7	33-12-12	TB0502Z	B013	1A		GD00508	AC..	1A		YC059-YR328
5734	20		PA		3-8	33-12-12	TB0501Z	B005	1A		GD00509	AC..	1A		YC053-YC058
5734	20		PA		3-10	33-12-12	TB0501Z	B005	1A		GD00509	AC..	1A		YC059-YC064
5734	20		PA		3-7	33-12-12	TB0501Z	B005	1A		GD00509	AC..	1A		YC065-YR328
5735	20		PA		1-3	33-12-12	TB0501V	A029	1		TB0501Z	A017	1A		YC053-YC064

WIRE LIST

D280A108

91-21-11

Section W2210

Page 39

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2218	286A2218				P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)										
5735	20		PA		1-8	33-12-12	TB0501V	A029	1		TB0501Z	A017	1A		YC065-YR328
5736	20		PA		4-6	33-12-12	TB0501V	B031	1		TB0507Z	B013	1A		YC053-YC058, YC065-YR328
5736	20		PA		4-1	33-12-12	TB0501V	B031	1		TB0507Z	B013	1A		YC059-YC064
5737	20		PA		1-3	33-12-12	TB0501V	B029	1		TB0501Z	B017	1A		YC053-YC064
5737	20		PA		1-8	33-12-12	TB0501V	B029	1		TB0501Z	B017	1A		YC065-YR328
5801	22		CQ		5-3	30-31-11	D00644		24		D40538P		9		YL968-YL999, YN236-YR328
5806	22		PA		5-3	30-31-11	D00644		23		D40538P		21		YL968-YL999, YN236-YR328
5807	22		PA		5-3	30-31-11	D00644		25		D40538P		22		YL968-YL999, YN236-YR328
5808	22		PA		5-3	30-31-11	D00644		36		D40538P		23		YL968-YL999, YN236-YR328
5809	22		CQ		18-2	30-31-11	D40538P		24		TB0608Y	A013	1A		YL968-YL999, YN236-YR328
5810	22		CQ		0-7	30-31-11	TB0608Y	A013	1A		TB0608Y	A015	1A		YL968-YL999, YN236-YR328
6001	22		PA		7-9	28-42-11	D00616		2		D40536P		16		YC051-YC052
6001	22		PA		7-5	28-42-11	D00616		2		D40536P		16		YC053-YC058
6001	22		PA		7-3	28-42-11	D00616		2		D40536P		16		YC059-YR328
6002	20		PA		3-5	28-42-11	D00616		5		GD00507	AC..	1A		YC051-YC052
6002	20		PA		3-1	28-42-11	D00616		5		GD00517	AC..	1A		YC053-YC058
6002	20		PA		3-0	28-42-11	D00616		5		GD00517	AC..	1A		YC059-YR328
6003	20		PA		20-5	28-42-11	D00616		3		D46114P		5		YC051-YC052
6003	20		PA		19-6	28-42-11	D00616		3		D46114P		5		YC053-YC058
6003	20		PA		19-4	28-42-11	D00616		3		D46114P		5		YC059-YC064
6003	20		PA		19-5	28-42-11	D00616		3		D46114P		5		YC065-YR328
6004	20		PA		20-5	28-42-11	D00616		4		D46114P		6		YC051-YC052
6004	20		PA		19-6	28-42-11	D00616		4		D46114P		6		YC053-YC058
6004	20		PA		19-4	28-42-11	D00616		4		D46114P		6		YC059-YC064
6004	20		PA		19-5	28-42-11	D00616		4		D46114P		6		YC065-YR328
6005	20		CQ		32-0	28-43-11	D40540P	B17			D00628		10		YD158-YR328
6006	22		PA		6-0	30-21-21	D00648		22		D40538P		6		YC051-YC052, YC059-YR328
6006	22		PA		6-1	30-21-21	D00648		22		D40538P		6		YC053-YC058
6007	20		PA		2-11	30-21-21	D00648		9		GD00506	DC..	1A		YC051-YC052
6007	20		PA		2-8	30-21-21	D00648		9		GD00506	DC..	1A		YC053-YC058
6007	20		PA		2-5	30-21-21	D00648		9		GD00506	DC..	1A		YC059-YR328

WIRE LIST

D280A108

91-21-11

Section W2210

Page 40

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity			
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice	
W2218	286A2218				P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)											
6009	24	PK		32-11	73-21-12	D03172		6			D40544P	A08			YC051-YC052	
6009	24	PK		32-4	73-21-12	D03172		6			D40544P	A08			YC053-YC055	
6009	24	PK		32-3	73-21-12	D03172		6			D40544P	A08			YC056-YC058, YC065-YR328	
6009	24	PK		32-1	73-21-12	D03172		6			D40544P	A08			YC059-YC064	
6010	24	PK		34-3	73-23-11	D00648		15			D40544P	B08			YC051-YC052	
6010	24	PK		33-5	73-23-11	D00648		15			D40544P	B08			YC053-YC058	
6010	24	PK		33-4	73-23-11	D00648		15			D40544P	B08			YC059-YR328	
6011	20	PA		2-11	73-23-11	D00648		19			GD00506	DC..	1A		YC051-YC052	
6011	20	PA		2-8	73-23-11	D00648		19			GD00506	DC..	1A		YC053-YC058	
6011	20	PA		2-5	73-23-11	D00648		19			GD00506	DC..	1A		YC059-YR328	
6012	24	PK		35-1	73-31-11	D00628		21			D40544P	A09			YC051-YC052	
6012	24	PK		34-1	73-31-11	D00628		21			D40544P	A09			YC053-YC055	
6012	24	PK		34-0	73-31-11	D00628		21			D40544P	A09			YC056-YC064	
6012	24	PK		34-2	73-31-11	D00628		21			D40544P	A09			YC065-YR328	
6013	24	PK		32-11	73-32-11	D03172		8			D40544P	B09			YC051-YC052	
6013	24	PK		32-4	73-32-11	D03172		8			D40544P	B09			YC053-YC055	
6013	24	PK		32-3	73-32-11	D03172		8			D40544P	B09			YC056-YC058, YC065-YR328	
6013	24	PK		32-1	73-32-11	D03172		8			D40544P	B09			YC059-YC064	
6014	20	PA		1-1	74-31-11	S00267		3B	C		GD00501	DC..	1A		YC051-YC052, YC056-YC058	
6014	20	PA		1-3	74-31-11	S00267		3B	C		GD00501	DC..	1A		YC053-YC055, YC059-YR328	
6015	20	PA		1-1	74-31-11	S00267		2B	C		GD00501	DC..	1A		YC051-YC052, YC056-YC058	
6015	20	PA		1-3	74-31-11	S00267		2B	C		GD00501	DC..	1A		YC053-YC055, YC059-YR328	
6016	24	PK		36-11	74-31-11	S00267		3A	C		D40544P	A10			YC051-YC052	
6016	24	PK		36-1	74-31-11	S00267		3A	C		D40544P	A10			YC053-YC055	
6016	24	PK		35-10	74-31-11	S00267		3A	C		D40544P	A10			YC056-YC058	
6016	24	PK		36-0	74-31-11	S00267		3A	C		D40544P	A10			YC059-YR328	
6017	24	PK		36-11	74-31-11	S00267		2A	C		D40544P	B10			YC051-YC052	
6017	24	PK		36-1	74-31-11	S00267		2A	C		D40544P	B10			YC053-YC055	
6017	24	PK		35-10	74-31-11	S00267		2A	C		D40544P	B10			YC056-YC058	
6017	24	PK		36-0	74-31-11	S00267		2A	C		D40544P	B10			YC059-YR328	
6019	24	PK		36-3	74-31-11	S00858		2	C		D40544P	B07			YC051-YC052	
6019	24	PK		35-3	74-31-11	S00858		2	C		D40544P	B07			YC053-YC055	
6019	24	PK		35-2	74-31-11	S00858		2	C		D40544P	B07			YC056-YR328	

WIRE LIST

D280A108

91-21-11

Section W2210

Page 41

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2218		286A2218			P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)										
	6020	20	PA		1-6	74-31-11	S00858	3	C		GD00501	DC..	1A		ALL
	6021	22	PA		32-11	78-36-21	D03172	19			D40544P	B06			YC051-YC052
	6021	22	PA		32-4	78-36-21	D03172	19			D40544P	B06			YC053-YC055
	6021	22	PA		32-3	78-36-21	D03172	19			D40544P	B06			YC056-YC058, YC065-YR328
	6021	22	PA		32-1	78-36-21	D03172	19			D40544P	B06			YC059-YC064
	6022	22	PA		6-0	30-21-21	D00648	17			D40538P	1			YC051-YC052, YC059-YR328
	6022	22	PA		6-1	30-21-21	D00648	17			D40538P	1			YC053-YC058
	6023	20	CQ		32-1	28-22-11	D40540P	A12			D00628	1			YC051-YC052
	6023	20	CQ		31-0	28-22-11	D40540P	A12			D00628	1			YC053-YC055
	6023	20	CQ		31-10	28-22-11	D40540P	A12			D00628	1			YC056-YC064
	6023	20	CQ		32-0	28-22-11	D40540P	A12			D00628	1			YC065-YR328
	6024	20	CQ		32-1	28-22-11	D40540P	A13			D00628	6			YC051-YC052
	6024	20	CQ		31-0	28-22-11	D40540P	A13			D00628	6			YC053-YC055
	6024	20	CQ		31-10	28-22-11	D40540P	A13			D00628	6			YC056-YC064
	6024	20	CQ		32-0	28-22-11	D40540P	A13			D00628	6			YC065-YR328
	6025	20	CQ		32-1	28-22-11	D40540P	A14			D00628	7			YC051-YC052
	6025	20	CQ		31-0	28-22-11	D40540P	A14			D00628	7			YC053-YC055
	6025	20	CQ		31-10	28-22-11	D40540P	A14			D00628	7			YC056-YC064
	6025	20	CQ		32-0	28-22-11	D40540P	A14			D00628	7			YC065-YR328
	6026	20	CQ		32-1	28-43-11	D40540P	A15			D00628	26			YC051-YC052
	6026	20	CQ		31-0	28-43-11	D40540P	A15			D00628	26			YC053-YC055
	6026	20	CQ		31-10	28-43-11	D40540P	A15			D00628	26			YC056-YC064
	6026	20	CQ		32-0	28-43-11	D40540P	A15			D00628	26			YC065-YR328
	6027	20	CQ		32-1	28-43-11	D40540P	B15			D00628	2			YC051-YC052
	6027	20	CQ		31-0	28-43-11	D40540P	B15			D00628	2			YC053-YC055
	6027	20	CQ		31-10	28-43-11	D40540P	B15			D00628	2			YC056-YC064
	6027	20	CQ		32-0	28-43-11	D40540P	B15			D00628	2			YC065-YR328
	6028	20	CQ		32-1	28-43-11	D40540P	B14			D00628	28			YC051-YC052
	6028	20	CQ		31-0	28-43-11	D40540P	B14			D00628	28			YC053-YC055
	6028	20	CQ		31-10	28-43-11	D40540P	B14			D00628	28			YC056-YC064
	6028	20	CQ		32-0	28-43-11	D40540P	B14			D00628	28			YC065-YR328
	6032	24	PK		8-9	74-31-11	S00267	5A	C		TB0262Y	A007	1A		YC051-YC055, YC059-YC064
	6032	24	PK		8-7	74-31-11	S00267	5A	C		TB0262Y	A007	1A		YC056-YC058
	6032	24	PK		9-2	74-31-11	S00267	5A	C		TB0262Y	A007	1A		YC065-YR328
	6033	24	PK		8-9	74-31-11	S00267	4A	C		TB0262Y	A007	1A		YC051-YC055, YC059-YC064

WIRE LIST

D280A108

91-21-11

Section W2210

Page 42

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W2218	286A2218				P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)											
6033	24	PK		8-7	74-31-11	S00267		4A	C		TB0262Y	A007	1A		YC056-YC058	
6033	24	PK		9-2	74-31-11	S00267		4A	C		TB0262Y	A007	1A		YC065-YR328	
6034	24	PK		8-9	74-31-11	S00267		4B	C		TB0262Y	B007	1A		YC051-YC055, YC059-YC064	
6034	24	PK		8-7	74-31-11	S00267		4B	C		TB0262Y	B007	1A		YC056-YC058	
6034	24	PK		9-2	74-31-11	S00267		4B	C		TB0262Y	B007	1A		YC065-YR328	
6035	24	PK		8-9	74-31-11	S00267		5B	C		TB0262Y	B007	1A		YC051-YC055, YC059-YC064	
6035	24	PK		8-7	74-31-11	S00267		5B	C		TB0262Y	B007	1A		YC056-YC058	
6035	24	PK		9-2	74-31-11	S00267		5B	C		TB0262Y	B007	1A		YC065-YR328	
6038	20	PA		19-8	30-21-21	D00648		13			D46114P		7		YC051-YC052	
6038	20	PA		18-10	30-21-21	D00648		13			D46114P		7		YC053-YR328	
6039	22	PA		19-8	30-21-21	D00648		11			D46114P		10		YC051-YC052	
6039	22	PA		18-10	30-21-21	D00648		11			D46114P		10		YC053-YR328	
6040	20	PA		32-1	28-23-11	D40540P		B11			D00628		37		YC051-YC052	
6040	20	PA		31-0	28-23-11	D40540P		B11			D00628		37		YC053-YC055	
6040	20	PA		31-10	28-23-11	D40540P		B11			D00628		37		YC056-YC064	
6040	20	PA		32-0	28-23-11	D40540P		B11			D00628		37		YC065-YR328	
6041	20	PA		32-1	28-23-11	D40540P		B12			D00628		35		YC051-YC052	
6041	20	PA		31-0	28-23-11	D40540P		B12			D00628		35		YC053-YC055	
6041	20	PA		31-10	28-23-11	D40540P		B12			D00628		35		YC056-YC064	
6041	20	PA		32-0	28-23-11	D40540P		B12			D00628		35		YC065-YR328	
6042	20	PA		32-1	28-23-11	D40540P		B13			D00628		39		YC051-YC052	
6042	20	PA		31-0	28-23-11	D40540P		B13			D00628		39		YC053-YC055	
6042	20	PA		31-10	28-23-11	D40540P		B13			D00628		39		YC056-YC064	
6042	20	PA		32-0	28-23-11	D40540P		B13			D00628		39		YC065-YR328	
6043	20	PA		7-1	28-23-11	GD00261		AC..	1A		D00628		38		YC051-YC052	
6043	20	PA		6-9	28-23-11	GD00261		AC..	1A		D00628		38		YC053-YC058	
6043	20	PA		6-10	28-23-11	GD00261		AC..	1A		D00628		38		YC059-YC064	
6043	20	PA		7-0	28-23-11	GD00261		AC..	1A		D00628		38		YC065-YD158	
6043	20	PA		6-11	28-23-11	GD00264		AC..	1A		D00628		38		YL951-YR328	
6044	20	PA		7-1	28-23-11	GD00261		AC..	1A		D00628		34		YC051-YC052	
6044	20	PA		6-9	28-23-11	GD00261		AC..	1A		D00628		34		YC053-YC058	
6044	20	PA		6-10	28-23-11	GD00261		AC..	1A		D00628		34		YC059-YC064	
6044	20	PA		7-0	28-23-11	GD00261		AC..	1A		D00628		34		YC065-YD158	
6044	20	PA		6-11	28-23-11	GD00264		AC..	1A		D00628		34		YL951-YR328	
6045	20	PA		7-1	28-23-11	GD00261		AC..	1A		D00628		36		YC051-YC052	
6045	20	PA		6-9	28-23-11	GD00261		AC..	1A		D00628		36		YC053-YC058	
6045	20	PA		6-10	28-23-11	GD00261		AC..	1A		D00628		36		YC059-YC064	

WIRE LIST

D280A108

91-21-11

Section W2210

Page 43

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2218		286A2218			P5 OVHD PANEL TO EE BAY (E3-1/E4-1/E4-2) RB2 (continued)											
6045		20		PA		7-0	28-23-11	GD00261	AC..	1A		D00628		36		YC065-YD158
6045		20		PA		6-11	28-23-11	GD00264	AC..	1A		D00628		36		YL951-YR328
6054		20		PA		32-0	28-23-11	D40540P	A01			D00628		18		YL951-YR328
6056		20		PA		6-11	28-23-11	GD00264	AC..	1A		D00628		9		YL951-YR328
6101		24		PK		26-0	21-31-11	TB0504Y	A003	1A		D40510P	B19			YD158-YR328
6102		24		PK		24-3	21-31-23	D10726		9		D40064P	A08			YD158-YR328
8001		22		PA		32-11	27-32-21	D02351		5		D40544P	A02			YC051-YC052
8001		22		PA		32-4	27-32-21	D02351		5		D40544P	A02			YC053-YC055
8001		22		PA		32-3	27-32-21	D02351		5		D40544P	A02			YC056-YC058
8001		22		PA		32-2	27-32-21	D02351		5		D40544P	A02			YC059-YC064
8001		22		PA		32-1	27-32-21	D02351		5		D40544P	A02			YC065-YR328
8002		20		PA		1-8	27-32-21	D02351		4		GD00508	DC..	1A		YC051-YC052
8002		20		PA		1-9	27-32-21	D02351		4		GD00508	DC..	1A		YC053-YR328
8003		22		PA		34-7	34-51-41	D01817		25		D40544P	A06			YC051-YC052
8003		22		PA		33-6	34-51-41	D01817		25		D40544P	A06			YC053-YC055, YC059-YR328
8003		22		PA		33-5	34-51-41	D01817		25		D40544P	A06			YC056-YC058
8004		20		PA		2-10	34-51-41	D01817		24		GD00507	DC..	1A		YC051-YC052
8004		20		PA		2-6	34-51-41	D01817		24		GD00517	DC..	1A		YC053-YC058
8004		20		PA		2-7	34-51-41	D01817		24		GD00517	DC..	1A		YC059-YR328
8005		20		PA		7-3	34-61-12	D40536P		2		D01817		7		YC051-YC052
8005		20		PA		6-10	34-61-12	D40536P		2		D01817		7		YC053-YC058
8005		20		PA		6-11	34-61-12	D40536P		2		D01817		7		YC059-YD157
8005		20		PA		4-0	34-61-12	D40536P		2		TB0503Y	B005	1A		YD158-YR328
8006		20		PA		27-4	SPARE	D40538P		4		D40542P	B20			YC051-YC052
8006		20		PA		27-1	SPARE	D40538P		4		D40542P	B20			YC053-YC055
8006		20		PA		26-10	SPARE	D40538P		4		D40542P	B20			YC056-YD170, YN501-YR328
A-AA						0-0	33-14-12	L00277	=P			SP00070		S		ALL
A-AB						0-0	33-14-12	L00277	=G			SP00072		S		ALL
FRAA						3-8	21-31-23	D10726			AA	GD00506	ST..	1A		YC052-YD170, YN231-YN501
FRAA						3-4	21-31-23	D10726			AA	GD00506	ST..	1A		YL951-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W2210

Page 44 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2221	286A2221			AUTOPILOT P9 TO E1-1											
0001	22		CQ		18-9	22-13-11	D40019P	A01			D04221P	1			ALL
0002	22		PA		6-11	22-14-11	D04221P	2			SM00001		S		ALL
0003	22		CQ		18-9	22-14-11	D40019P	A03			D04221P	3			ALL
0004	22		CQ		18-9	22-14-11	D40019P	A04			D04221P	4			ALL
0005	22		PA		18-9	22-14-11	D40019P	A05			D04221P	5			ALL
0006	22		PA		18-9	22-14-11	D40019P	A06			D04221P	6			ALL
0007	22		PA		21-9	22-14-11	TB0806Y	B011	1A		D04221P	7			ALL
0008	22		CQ		18-9	22-31-11	D40019P	A08			D04221P	8			YC051-YD155
0008	22		CQ		18-9	22-14-11	D40019P	A08			D04221P	8			YD157-YR328
0009	22		PA		18-9	22-31-51	D40019P	A09			D04221P	9			ALL
0010	22		PA		18-9	34-61-16	D40019P	A10			D04221P	10			ALL
0011	22		PA		18-9	34-61-16	D40019P	B01			D04221P	11			ALL
0012	24		PK		18-9	34-49-11	D40019P	A02			D04221P	45			YC053-YD170
0012	24		PK		18-9	34-49-11	D04221P	45			D40019P	A02			YL951-YR328
0015	24		B6		18-9	27-81-31	D04221P	15			D40019P	B05			ALL
0016	24		B6		18-9	27-81-31	D40019P	B06			D04221P	16			ALL
0017	22		PA		15-10	22-14-11	SM00001		S		TB0806Y	A011	1A		ALL
0020	22		PA		12-10	22-14-11	D40019P	B10			SM00001		S		ALL
0031	24		PK		21-9	23-51-11	D04221P	31			TB0806Y	A003	1A		YL951-YR328
0032	24		PK		21-9	23-51-11	D04221P	32			TB0806Y	B001	1A		YL951-YR328
0111	24		PK		18-9	34-49-11	D40019P	A11			D04221P	12			ALL
0112	24		PK		18-9	34-49-11	D40019P	A12			D04221P	17			ALL
0113	24		PK		18-9	34-49-11	D40019P	A13			D04221P	25			ALL
0114	24		PK		18-9	34-49-11	D40019P	A14			D04221P	27			ALL
0115	24		PK		18-9	34-49-11	D40019P	A15			D04221P	28			ALL
0116	24		PK		18-9	34-49-11	D40019P	A16			D04221P	29			ALL
0118	22		PA		18-9	32-31-11	D40019P	A18			D04221P	38			ALL
0119	22		CQ		18-9	27-54-11	D04221P	13			D40019P	A07			ALL
0120	24		PK		18-4	34-49-11	D04221P	18			D40133P	A07			YL956-YL999, YN236-YR328
0121	24		PK		18-4	34-49-11	D04221P	19			D40133P	B03			YL956-YL999, YN236-YR328
0211	22		PA		18-9	34-45-11	D40019P	B11			D04221P	30			ALL
2001B	24		Y2	AA	18-9	31-62-11	D04221P	44			D40019P	B20			ALL
2001R	24		Y2	AA	0-0	31-62-11	D04221P	43			D40019P	B19			ALL
2001Z				AA	0-0	31-62-11	D04221P	S/R			D40019P	PERG	1F		ALL
2013B	24		Y2	AM	18-9	31-22-11	D40019P	B14			D04221P	34			ALL
2013R	24		Y2	AM	0-0	31-22-11	D40019P	B13			D04221P	33			ALL
2013Z				AM	0-0	31-22-11	D40019P	PERG	1F		D04221P	S/R			ALL

WIRE LIST

D280A108

91-21-11

Section W2220

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2221		286A2221			AUTOPILOT P9 TO E1-1 (continued)											
2015B		24		Y2	AP	18-9	31-22-11	D40019P	B16			D04221P	36			ALL
2015R		24		Y2	AP	0-0	31-22-11	D40019P	B15			D04221P	35			ALL
2015Z					AP	0-0	31-22-11	D40019P	PERG	1F		D04221P	S/R			ALL
2019B		24		Y2	AS	18-9	31-62-12	D40019P	A20			D04221P	40			ALL
2019R		24		Y2	AS	0-0	31-62-12	D40019P	A19			D04221P	39			ALL
2019Z					AS	0-0	31-62-12	D40019P	PERG	1F		D04221P	S/R			ALL
2121B		24		Y2	BA	18-9	27-52-11	D40019P	B03			D04221P	22			ALL
2121R		24		Y2	BA	0-0	27-52-11	D40019P	B02			D04221P	21			ALL
2121Z					BA	0-0	27-52-11	D40019P	B04			D04221P	S/R			ALL
2141B		24		Y2	BB	18-9	27-52-11	D40019P	B18			D04221P	42			ALL
2141R		24		Y2	BB	0-0	27-52-11	D40019P	B17			D04221P	41			ALL
2141Z					BB	0-0	27-52-11	D40019P	A17			D04221P	S/R			ALL
3147B		20		X3	CA	18-9	27-52-11	D40019P	B08			D04221P	48			ALL
3147R		20		X3	CA	0-0	27-52-11	D40019P	B07			D04221P	47			ALL
3147Y		20		X3	CA	0-0	27-52-11	D40019P	B09			D04221P	49			ALL
3147Z					CA	0-0	27-52-11	D40019P	B12			D04221P	S/R			ALL

WIRE LIST

D280A108

91-21-11

Section W2220

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2231	286A2231				RIGHT AC ELEX PWR FROM P6 TO E3.										
0001	20		PA		22-1	34-61-11	D46067P				D46017P	1			YC051-YC055
0001	20		PA		22-0	34-61-11	D46067P				D46017P	1			YC056-YN236, YN501-YR328
0002	20		PA		22-1	34-61-11	D46067P				D46017P	2			YC051-YC055
0002	20		PA		22-0	34-61-11	D46067P				D46017P	2			YC056-YN236, YN501-YR328
0003	22		CQ		22-1	34-57-21	D46067P				D46017P	3			YC051-YC055
0003	22		CQ		22-0	34-57-21	D46067P				D46017P	3			YC056-YN236, YN501-YR328
0004	22		PA		23-7	27-32-21	D46067P				D46021P	4			YC051-YC055
0004	22		PA		23-6	27-32-21	D46067P				D46021P	4			YC056-YN236, YN501-YR328
0005	22		CQ		23-7	34-33-21	D46067P				D46021P	5			YC051-YC055
0005	22		CQ		23-6	34-33-21	D46067P				D46021P	5			YC056-YN236, YN501-YR328
0006	20		PA		22-1	SPARE	D46067P				D46017P	6			YC051-YC055
0006	20		PA		22-0	SPARE	D46067P				D46017P	6			YC056-YN236, YN501-YR328
0007	20		PA		22-1	SPARE	D46067P				D46017P	7			YC051-YC055
0007	20		PA		22-0	SPARE	D46067P				D46017P	7			YC056-YN236, YN501-YR328
0008	20		CQ		23-7	22-23-11	D46067P				D46021P	8			YC051-YC055
0008	20		CQ		23-6	22-23-11	D46067P				D46021P	8			YC056-YN236, YN501-YR328
0009	20		PA		23-7	SPARE	D46067P				D46021P	9			YC051-YC055
0009	20		PA		23-6	SPARE	D46067P				D46021P	9			YC056-YN236, YN501-YR328
0010	20		PA		23-7	SPARE	D46067P				D46021P	10			YC051-YC055
0010	20		PA		23-6	SPARE	D46067P				D46021P	10			YC056-YN236, YN501-YR328
0011	20		PA		23-7	SPARE	D46067P				D46021P	11			YC051-YC055
0011	20		PA		23-6	SPARE	D46067P				D46021P	11			YC056-YN236, YN501-YR328
0012	20		PA		23-7	SPARE	D46067P				D46021P	12			YC051-YC055
0012	20		PA		23-6	SPARE	D46067P				D46021P	12			YC056-YN236, YN501-YR328
0013	22		CQ		23-10	23-27-11	D46067P				D43309P	3			YC051-YC055
0013	22		CQ		23-9	23-27-11	D46067P				D43309P	3			YC056-YD157

WIRE LIST

D280A108

91-21-11

Section W2230

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W2231	286A2231				RIGHT AC ELEX PWR FROM P6 TO E3. (continued)												
0013	22		CQ		23-9		23-27-31	D46067P		13		D43309P		3		YD158-YN236, YN501-YR328	
0015	16		CQ		23-10		23-12-31	D46067P		15		D43309P		4		YC051-YC055	
0015	16		CQ		23-9		23-12-31	D46067P		15		D43309P		4		YC056-YL999, YN501-YR328	
0015	16		PA		23-9		23-12-31	D46067P		15		D43309P		4		YN231-YN236	
0016	20		PA		30-0		27-32-21	D46021P		6		SP00091			S	YC051-YC055	
0016	20		PA		29-11		27-32-21	D46021P		6		SP00091			S	YC056-YN236, YN501-YR322	
0016	20		PA		28-6		27-32-21	D46021P		6		SP00091			S	YR323-YR328	
0019	16		CQ		23-10		23-12-31	D46067P		19		D43309P		7		YC051-YC055	
0019	16		CQ		23-9		23-12-31	D46067P		19		D43309P		7		YC056-YD157	
0019	16		CQ		23-9		SPARE	D46067P		19		D43309P		7		YD158-YL999, YN501-YR328	
0019	16		PA		23-9		SPARE	D46067P		19		D43309P		7		YN231-YN236	
0021	20		PA		23-10		SPARE	D46067P		21		D43309P		1		YC051-YC055	
0021	20		PA		23-9		SPARE	D46067P		21		D43309P		1		YC056-YL999, YN501	
0022	20		PA		23-10		SPARE	D46067P		22		D43309P		2		YC051-YC055	
0022	20		PA		23-9		SPARE	D46067P		22		D43309P		2		YC056-YL999, YN501	
0023	16		PA		23-10		SPARE	D46067P		23		D43309P		10		YC051-YC055	
0023	16		PA		23-9		SPARE	D46067P		23		D43309P		10		YC056-YL999, YN501	
0025	20		PA		23-10		SPARE	D46067P		25		D43309P		5		YC051-YC055	
0025	20		PA		23-9		SPARE	D46067P		25		D43309P		5		YC056-YL999, YN501	
0026	20		PA		23-10		SPARE	D46067P		26		D43309P		6		YC051-YC055	
0026	20		PA		23-9		SPARE	D46067P		26		D43309P		6		YC056-YL999, YN501	
0027	16		PA		22-1		SPARE	D46067P		27		D46017P		7		YC051-YC055	
0027	16		PA		22-0		SPARE	D46067P		27		D46017P		7		YC056-YN236, YN501-YR328	
0028	20		PA		22-1		SPARE	D46067P		28		D46017P		8		YC051-YC055	
0028	20		PA		22-0		SPARE	D46067P		28		D46017P		8		YC056-YN236, YN501-YR328	
W2237	286A2237				SECONDARY CDS-DEU TO P3												
0003	22		PA		28-4		SPARE	D04237P		13		D04297P		A13		YC051-YC055	
0003	22		PA		28-7		SPARE	D04237P		13		D04297P		A13		YC056-YR328	
0004	22		PA		28-4		SPARE	D04237P		14		D04297P		A14		YC051-YC055	
0004	22		PA		28-7		SPARE	D04237P		14		D04297P		A14		YC056-YR328	
0005	22		PA		24-10		30-31-11	D04297P		B08		TB0608Y		B013	1A	YL968-YL999, YN236-YR328	

WIRE LIST

D280A108

91-21-11

Section W2230

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2237	286A2237			SECONDARY CDS-DEU TO P3 (continued)											
0006	22		PA		24-10	30-31-11	D04297P	B15			TB0608Y	B015	1A		YL968-YL999, YN236-YR328
0013	22		PA		23-0	34-41-11	D40099P	A06			D04297P	B13			YC051-YC052
0014	22		PA		23-0	34-41-11	D40099P	A07			D04297P	B14			YC051-YC052
0029	22		PA		28-4	SPARE	D04237P	29			D04297P	B09			YC051-YC055
0029	22		PA		28-7	SPARE	D04237P	29			D04297P	B09			YC056-YR328
0030	22		PA		28-4	SPARE	D04237P	30			D04297P	B10			YC051-YC055
0030	22		PA		28-7	SPARE	D04237P	30			D04297P	B10			YC056-YR328
0031	22		PA		28-4	SPARE	D04237P	31			D04297P	B11			YC051-YC055
0031	22		PA		28-7	SPARE	D04237P	31			D04297P	B11			YC056-YR328
0032	22		PA		28-4	SPARE	D04237P	32			D04297P	B12			YC051-YC055
0032	22		PA		28-7	SPARE	D04237P	32			D04297P	B12			YC056-YR328
0033	22		PA		13-10	34-41-11	D04237P	33			D40099P	A05			YC051-YC052
0037	22		PA		28-4	SPARE	D04237P	37			D04297P	B17			YC051-YC055
0037	22		PA		28-7	SPARE	D04237P	37			D04297P	B17			YC056-YR328
0038	22		PA		28-4	SPARE	D04237P	38			D04297P	B18			YC051-YC055
0038	22		PA		28-7	SPARE	D04237P	38			D04297P	B18			YC056-YR328
0040	22		CQ		28-4	SPARE	D04237P	40			D04297P	B19			YC051-YC055
0040	22		CQ		28-7	SPARE	D04237P	40			D04297P	B19			YC056-YR328
0041	22		CQ		28-4	SPARE	D04237P	41			D04297P	B20			YC051-YC055
0041	22		CQ		28-7	SPARE	D04237P	41			D04297P	B20			YC056-YR328
2001B	24		Y2	AA	28-4	31-62-22	D04237P	2			D04297P	A02			YC051-YC055
2001B	24		Y2	AA	28-7	31-62-22	D04237P	2			D04297P	A02			YC056-YR328
2001R	24		Y2	AA	0-0	31-62-22	D04237P	1			D04297P	A01			ALL
2001Z				AA	0-0	31-62-22	D04237P	S/R			D04297P	PERG	1F		ALL
2002B	24		Y2	AB	28-4	31-62-22	D04237P	4			D04297P	A04			YC051-YC055
2002B	24		Y2	AB	28-7	31-62-22	D04237P	4			D04297P	A04			YC056-YR328
2002R	24		Y2	AB	0-0	31-62-22	D04237P	3			D04297P	A03			ALL
2002Z				AB	0-0	31-62-22	D04237P	S/R			D04297P	PERG	1F		ALL
2003B	24		Y2	AC	28-4	SPARE	D04237P	6			D04297P	A06			YC051-YC055
2003B	24		Y2	AC	28-7	SPARE	D04237P	6			D04297P	A06			YC056-YR328
2003R	24		Y2	AC	0-0	SPARE	D04237P	5			D04297P	A05			ALL
2003Z				AC	0-0	SPARE	D04237P	S/R			D04297P	PERG	1F		ALL
2004B	24		Y2	AD	28-4	SPARE	D04237P	8			D04297P	A08			YC051-YC055
2004B	24		Y2	AD	28-7	SPARE	D04237P	8			D04297P	A08			YC056-YR328
2004R	24		Y2	AD	0-0	SPARE	D04237P	7			D04297P	A07			ALL
2004Z				AD	0-0	SPARE	D04237P	S/R			D04297P	PERG	1F		ALL
2005B	24		Y2	AE	28-4	31-62-23	D04237P	10			D04297P	A10			YC051-YC055
2005B	24		Y2	AE	28-7	31-62-23	D04237P	10			D04297P	A10			YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W2230

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2237		286A2237			SECONDARY CDS-DEU TO P3 (continued)											
2005R		24		Y2	AE	0-0	31-62-23	D04237P		9		D04297P	A09			ALL
2005Z					AE	0-0	31-62-23	D04237P		S/R		D04297P	PERG	1F		ALL
2006B		24		Y2	AF	13-10	31-62-23	D04237P		12		D40099P	A02			YC051-YC052
2006R		24		Y2	AF	0-0	31-62-23	D04237P		11		D40099P	A01			YC051-YC052
2006Z					AF	0-0	31-62-23	D04237P		S/R		D40099P	PERG	1F		YC051-YC052
2007B		24		7K	AG	23-0	34-41-11	D04297P		A12		D40099P	A04			YC051-YC052
2007W		24		7K	AG	0-0	34-41-11	D04297P		A11		D40099P	A03			YC051-YC052
2007Z					AG	0-0	34-41-11	D04297P		PERG	1F	D40099P	PERG	1F		YC051-YC052
2008B		24		Y2	AH	28-4	SPARE	D04237P		16		D04297P	A16			YC051-YC055
2008B		24		Y2	AH	28-7	SPARE	D04237P		16		D04297P	A16			YC056-YR328
2008R		24		Y2	AH	0-0	SPARE	D04237P		15		D04297P	A15			ALL
2008Z					AH	0-0	SPARE	D04237P		S/R		D04297P	PERG	1F		ALL
2009B		24		Y2	AJ	28-4	SPARE	D04237P		18		D04297P	A18			YC051-YC055
2009B		24		Y2	AJ	28-7	SPARE	D04237P		18		D04297P	A18			YC056-YR328
2009R		24		Y2	AJ	0-0	SPARE	D04237P		17		D04297P	A17			ALL
2009Z					AJ	0-0	SPARE	D04237P		S/R		D04297P	PERG	1F		ALL
2010B		24		Y2	AK	28-4	SPARE	D04237P		20		D04297P	A20			YC051-YC055
2010B		24		Y2	AK	28-7	SPARE	D04237P		20		D04297P	A20			YC056-YR328
2010R		24		Y2	AK	0-0	SPARE	D04237P		19		D04297P	A19			ALL
2010Z					AK	0-0	SPARE	D04237P		S/R		D04297P	PERG	1F		ALL
2011B		24		Y2	AL	28-4	SPARE	D04237P		22		D04297P	B02			YC051-YC055
2011B		24		Y2	AL	28-7	SPARE	D04237P		22		D04297P	B02			YC056-YR328
2011R		24		Y2	AL	0-0	SPARE	D04237P		21		D04297P	B01			ALL
2011Z					AL	0-0	SPARE	D04237P		S/R		D04297P	PERG	1F		ALL
2012B		24		Y2	AM	28-4	SPARE	D04237P		24		D04297P	B04			YC051-YC055
2012B		24		Y2	AM	28-7	SPARE	D04237P		24		D04297P	B04			YC056-YR328
2012R		24		Y2	AM	0-0	SPARE	D04237P		23		D04297P	B03			ALL
2012Z					AM	0-0	SPARE	D04237P		S/R		D04297P	PERG	1F		ALL
2013B		24		Y2	AN	23-0	34-41-11	D40099P		A09		D04297P	B06			YC051-YC052
2013R		24		Y2	AN	0-0	34-41-11	D40099P		A08		D04297P	B05			YC051-YC052
2013Z					AN	0-0	34-41-11	D40099P		PERG	1F	D04297P	PERG	1F		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W2230

Page 4 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2247	286A2247				ATC NO.2 (E1-5 TO P8-29)										
0003	20		PA		15-1	34-53-21	D00519		3		D41517J		3		YC051-YN236, YN501-YR328
0004	20		PA		4-0	34-53-21	D00519		4		GD00811	AC..	1A		YC051-YN236, YN501-YR328
0005	22		PA		10-3	34-53-31	D00519		5		D40103P	A06			YC051-YN236, YN501-YR328
0006	20		PA		3-11	34-53-21	D00519		6		GD00803	DC..	1A		YC051-YN236, YN501-YR328
0007	24		PK		10-3	34-53-21	D00519		7		D40103P	A02			YC051-YC052
0007	24		PK		15-1	34-53-21	D00519		7		D41517J	7			YC053-YN236, YN501-YR328
0008	20		PA		4-0	34-53-21	D00519		8		GD00811	DC..	1A		YC051-YN236, YN501-YR328
0009	20		PA		15-1	34-53-21	D00519		9	VP	D41517J	9			YC051-YN236, YN501-YR328
0010	20		PA		15-1	34-53-21	D00519		10	VP	D41517J	10			YC051-YN236, YN501-YR328
0011	24		PK		15-1	34-53-21	D00519		11		D41517J	11			YC051-YN236, YN501-YR328
0012	24		PK		15-1	34-53-21	D00519		12		D41517J	12			YC051-YN236, YN501-YR328
0013	20		PA		1-10	34-53-31	D10204		B		GD01111	DC..	E		YC051-YN236, YN501-YR328
0014	22		PA		14-11	34-53-31	D10204		A		D40103P	A05			YC051-YN236, YN501-YR328
0015	24		PK		15-1	34-53-21	D00519		15		D41517J	15			YC051-YN236, YN501-YR328
0016	24		PK		15-1	34-53-21	D00519		16		D41517J	6			YC051-YN236, YN501-YR328
0020	24		PK		15-1	34-53-21	D00519		20		D41517J	1			YC051-YN236, YN501-YR328
0024	22		PA		10-3	34-53-21	D00519		24		D40103P	A01			YC051-YN236, YN501-YR328
0025	22		PA		14-11	34-53-31	D10204		C		D40103P	A07			YC051-YN236, YN501-YR328
0026	22		PA		14-9	34-53-31	D10206		C		D40103P	A08			YC051-YN236, YN501-YR328
0027	22		PA		14-9	34-53-31	D10206		A		D40103P	A04			YC051-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W2240

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2247	286A2247			ATC NO.2 (E1-5 TO P8-29) (continued)											
0028	20		PA		1-3	34-53-31	D10206	B			GD01111	DC..	E		YC051-YN236, YN501-YR328
0029	20		PA		4-0	34-53-21	D00519			FL	GD00801	ST..	1A		YR312-YR328
0037	24		PK		14-4	34-53-21	D41517J	7			D40103P	A03			YC051-YC052
2001B	24		Y2	AA	15-1	34-53-21	D00519	23			D41517J	14			YC051-YN236, YN501-YR328
2001R	24		Y2	AA	0-0	34-53-21	D00519	22			D41517J	13			YC051-YN236, YN501-YR328
2001Z				AA	0-0	34-53-21	D00519	DED			D41517J	S/R			YC051-YN236, YN501-YR309
2001Z				AA	0-0	34-53-21	D00519			FL	D41517J	S/R			YR312-YR328

WIRE LIST

D280A108

91-21-11

Section W2240

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2251	286A2251			AUTOPILOT P3 TO E1-4											
0001	22		PA		17-5	22-13-11	D04311J		1		D04251P		1		ALL
0002	22		PA		17-5	22-14-11	D04311J		2		D04251P		2		ALL
0003	22		PA		17-5	SPARE	D04311J		3		D04251P		3		ALL
0004	22		PA		17-5	22-14-11	D04311J		4		D04251P		4		ALL
0005	22		PA		17-5	22-14-11	D04311J		5		D04251P		5		ALL
0006	22		CQ		17-5	22-14-11	D04311J		6		D04251P		6		ALL
0007	22		CQ		17-5	22-31-11	D04311J		7		D04251P		7		YC051-YD155
0007	22		CQ		17-5	SPARE	D04311J		7		D04251P		7		YD157-YR328
0008	22		CQ		17-5	22-31-51	D04311J		8		D04251P		8		ALL
0009	22		CQ		17-5	SPARE	D04311J		9		D04251P		9		ALL
0010	22		CQ		17-5	34-61-16	D04311J		10		D04251P		10		ALL
0011	22		CQ		17-5	22-14-11	D04311J		11		D04251P		11		ALL
0012	20		PA		17-5	SPARE	D04311J		12		D04251P		12		ALL
0013	24		B6		14-7	23-51-21	D04251P		23		TB0805Y	B011	1A		YL951-YR328
0014	24		B6		14-7	23-51-21	D04251P		24		TB0805Y	A011	1A		YL951-YR328
0024	22		CQ		17-5	SPARE	D04311J		24		D04251P		24		YC051-YD170
2001B	24		Y2	AA	17-5	31-62-22	D04251P		14		D04311J		14		ALL
2001R	24		Y2	AA	0-0	31-62-22	D04251P		13		D04311J		13		ALL
2001Z				AA	0-0	31-62-22	D04251P		S/R		D04311J		S/R		ALL
2002B	24		Y2	AB	17-5	31-62-21	D04251P		18		D04311J		18		ALL
2002R	24		Y2	AB	0-0	31-62-21	D04251P		17		D04311J		17		ALL
2002Z				AB	0-0	31-62-21	D04251P		S/R		D04311J		S/R		ALL
2003B	24		Y2	AC	17-5	SPARE	D04251P		20		D04311J		20		ALL
2003R	24		Y2	AC	0-0	SPARE	D04251P		19		D04311J		19		ALL
2003Z				AC	0-0	SPARE	D04251P		S/R		D04311J		S/R		ALL
2004B	24		Y2	AD	17-5	SPARE	D04251P		22		D04311J		22		ALL
2004R	24		Y2	AD	0-0	SPARE	D04251P		21		D04311J		21		ALL
2004Z				AD	0-0	SPARE	D04251P		S/R		D04311J		S/R		ALL
2007B	24		Y2	AG	17-5	34-58-21	D04311J		16		D04251P		16		YC053-YR328
2007R	24		Y2	AG	0-0	34-58-21	D04311J		15		D04251P		15		YC053-YR328
2007Z				AG	0-0	34-58-21	D04311J		S/R		D04251P		S/R		YC053-YR328

WIRE LIST

D280A108

91-21-11
Section W2250
Page 1 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2265		286A2265			ADF-1 ELEX PNL TO E3-1											
0001		20		PA		3-10	34-57-11	D03655		7		GD00811	ST..	1A		YC051-YL956, YL958-YR328
0001		20		PA		3-10	34-57-11	D03659		7		GD00811	ST..	1A		YL957
0002		20		PA		28-8	34-57-11	D03655		10		D42005P	A01			YC051-YC055
0002		20		PA		29-6	34-57-11	D03655		10		D42005P	A01			YC056-YL956, YL958-YR328
0002		20		PA		29-6	34-57-11	D03659		10		D42005P	A01			YL957
0003		22		PA		28-8	34-57-11	D03655		9		D42005P	A09			YC051-YC055
0003		22		PA		29-6	34-57-11	D03655		9		D42005P	A09			YC056-YL956, YL958-YR328
0003		22		PA		29-6	34-57-11	D03659		9		D42005P	A09			YL957
0004		20		PA		3-10	34-57-11	D03655		8		GD00811	AC..	1A		YC051-YL956, YL958-YR328
0004		20		PA		3-10	34-57-11	D03659		8		GD00811	AC..	1A		YL957
0005		20		PA		4-6	33-11-33	D03655		1		TB0801W	B021	1		YC051-YL956, YL958-YR328
0005		20		PA		4-6	33-11-33	D03659		1		TB0801W	B021	1		YL957
0006		20		PA		4-1	33-11-33	D03655		2		GD00805	AC..	1A		YC051-YL956, YL958-YR328
0006		20		PA		4-1	33-11-33	D03659		2		GD00805	AC..	1A		YL957
0007		20		CQ		4-9	33-18-62	D03655		4		TB0804Z	A017	1A		YC051-YC064, YC067-YC068
0007		20		CQ		4-9	33-18-62	D03655		4		SP00321		9		YC065
0007		20		CQ		6-4	33-18-62	D03655		4		SP00321		9		YC070-YL956, YL958-YR328
0007		20		CQ		6-4	33-18-62	D03659		4		SP00321		9		YL957
0008		20		CQ		10-0	33-18-62	TB0803Y	B015	1A		SP00321		9		YC065
0008		20		CQ		4-8	33-18-62	TB0803Y	B015	1A		SP00321		9		YC070-YR328
2001B		24		Y2	AA	28-8	34-57-11	D03655		13		D42005P	A03			YC051-YC055
2001B		24		Y2	AA	29-6	34-57-11	D03655		13		D42005P	A03			YC056-YL956, YL958-YR328
2001B		24		Y2	AA	29-6	34-57-11	D03659		13		D42005P	A03			YL957
2001R		24		Y2	AA	0-0	34-57-11	D03655		12		D42005P	A02			YC051-YL956, YL958-YR328
2001R		24		Y2	AA	0-0	34-57-11	D03659		12		D42005P	A02			YL957
2001Z					AA	0-0	34-57-11	D03655		S/R		D42005P	PERG	1F		YC051-YL956, YL958-YR328
2001Z					AA	0-0	34-57-11	D03659		S/R		D42005P	PERG	1F		YL957

WIRE LIST

D280A108

91-21-11

Section W2260

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From		Term	Type	Splice	To		Term	Type	Splice	Effectivity
	GA	CO	TY		FT-IN	Diagram	Equip	Equip				Equip					
W2267	286A2267				ADF-2 ELEX PNL TO E3-1												
0001	20		PA		4-2	34-57-21		D03657		7		GD00811	ST..	1A			YC051-YD157, YD160-YL956, YL958-YR328
0001	20		PA		4-3	34-57-21		D03657		7		GD00811	ST..	1A			YD158
0001	20		PA		4-2	34-57-21		D03661		7		GD00811	ST..	1A			YL957
0002	20		PA		28-11	34-57-21		D03657		10		D42007P	A01				YC051-YC055
0002	20		PA		28-10	34-57-21		D03657		10		D42007P	A01				YC056-YL956, YL958-YR328
0002	20		PA		28-10	34-57-21		D03661		10		D42007P	A01				YL957
0003	22		PA		28-11	34-57-21		D03657		9		D42007P	A09				YC051-YC055
0003	22		PA		28-10	34-57-21		D03657		9		D42007P	A09				YC056-YL956, YL958-YR328
0003	22		PA		28-10	34-57-21		D03661		9		D42007P	A09				YL957
0004	20		PA		4-2	34-57-21		D03657		8		GD00811	AC..	1A			YC051-YD157, YD160-YL956, YL958-YR328
0004	20		PA		4-3	34-57-21		D03657		8		GD00811	AC..	1A			YD158
0004	20		PA		4-2	34-57-21		D03661		8		GD00811	AC..	1A			YL957
0005	20		PA		4-0	33-11-41		D03657		1		TB0801W	A017	1			YC051-YD157
0005	20		PA		4-1	33-11-41		D03657		1		TB0801W	B013	1			YD158
0005	20		PA		4-0	33-11-41		D03657		1		TB0801V	A009	1			YD160-YL956, YL958-YR328
0006	20		PA		4-0	33-11-41		D03657		2		GD00805	AC..	1A			YC051-YL956, YL958-YR328
0007	20		CQ		4-4	33-18-62		D03657		4		TB0804Z	A017	1A			YC051-YD157, YD160-YL956, YL958-YR328
0007	20		CQ		4-5	33-18-62		D03657		4		TB0804Z	A017	1A			YD158
0007	20		CQ		4-4	33-18-62		D03661		4		TB0804Z	A017	1A			YL957
2001B	24		Y2	AA	28-11	34-57-21		D03657		13		D42007P	A03				YC051-YC055
2001B	24		Y2	AA	28-10	34-57-21		D03657		13		D42007P	A03				YC056-YL956, YL958-YR328
2001B	24		Y2	AA	28-10	34-57-21		D03661		13		D42007P	A03				YL957
2001R	24		Y2	AA	0-0	34-57-21		D03657		12		D42007P	A02				YC051-YL956, YL958-YR328
2001R	24		Y2	AA	0-0	34-57-21		D03661		12		D42007P	A02				YL957
2001Z				AA	0-0	34-57-21		D03657		S/R		D42007P	PERG	1F			YC051-YL956, YL958-YR328
2001Z				AA	0-0	34-57-21		D03661		S/R		D42007P	PERG	1F			YL957

WIRE LIST

D280A108

91-21-11

Section W2260

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2307		286A2307					HANDSET/MIC JACK - CONTROL STAND (P8)									
0001		22		PA		13-9	23-31-01	D04149P	1			D07015	= 1	VR		ALL
0002		20		PA		2-6	23-31-01	GD00803	DC..	1A		D07021	= 1	VY		ALL
2001B		22		X2	AA	13-9	23-31-01	D04149P	3			D07019	= 1	VG		ALL
2001R		22		X2	AA	0-0	23-31-01	D04149P	2			D07017	= 1	VS		ALL
2001Z					AA	0-0	23-31-01	D04149P			AA	D07017	DED			ALL
3501B		24		Y3	AB	14-1	23-42-12	D04149P	5			SM00003		S		ALL
3501R		24		Y3	AB	0-0	23-42-12	D04149P	4			SM00001		S		ALL
3501Y		24		Y3	AB	0-0	23-42-12	D04149P	6			SM00005		S		ALL
3501Z					AB	0-0	23-42-12	D04149P			AA	SM00001	DED			ALL
A-A						0-0	23-42-12	SM00001		S		D06019	RED			ALL
A-B						0-0	23-42-12	SM00003		S		D06019	BLU			ALL
A-C						0-0	23-42-12	SM00005		S		D06019	BLK			ALL
FRAA						0-0	23-42-12	D04149P	7			D04149P			AA	ALL

WIRE LIST

D280A108

91-21-11

Section W2300

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2363	286A2363				AUTO PILOT CONTROL PANEL SYSTEM A										
1001	20	X1	A		3-6	22-11-11	D00299	44			GD00981	DC..	E	*	ALL
1001Z			A		0-0	22-11-11	D00299	S/R			GD00977	ST..	E	*1	ALL
1002	20	X1	B		3-6	22-11-11	D00299	5			GD00981	DC..	E		ALL
1002Z			B		0-0	22-11-11	D00299	S/R			GD00977	ST..	E	*1	ALL
1003	22	X1	C		24-5	22-11-11	D04069P	B03			D00299	43			ALL
1003Z			C		0-0	22-11-11	D04069P	PERG	1F		D00299	S/R			ALL
1004	22	X1	D		24-5	22-14-11	D04069P	A11			D00299	47			ALL
1004Z			D		0-0	22-14-11	D04069P	PERG	1F		D00299	S/R			YC051-YD155
1004Z			D		0-0	22-14-11	D04069P			AC	D00299	S/R			YD157-YR328
1005	20	X1	E		3-6	22-11-11	D00299	55			GD00981	DC..	E	*	ALL
1005Z			E		0-0	22-11-11	D00299	S/R			GD00977	ST..	E	*1	ALL
1006	22	X1	F		24-5	22-31-51	D00301	8			D04069P	A12			ALL
1006Z			F		0-0	22-31-51	D00301	S/R			D04069P	PERG	1F		ALL
1007	22	X1	AB		24-5	22-14-11	D04069P	A14			D00299	20			YD157-YR328
1007Z			AB		0-0	22-14-11	D04069P			AC	D00299	S/R			YD157-YR328
1008	22	X1	H		24-5	22-31-51	D04069P	A13			D00301	7			ALL
1008Z			H		0-0	22-31-51	D04069P	PERG	1F		D00301	S/R			ALL
1009	22	X1	I		24-5	22-31-51	D00301	13			D04069P	B12			ALL
1009Z			I		0-0	22-31-51	D00301	S/R			D04069P	PERG	1F		ALL
1010	20	X1	J		24-5	22-12-31	D04069P	B06			D00299	16			ALL
1010Z			J		0-0	22-12-31	D04069P	PERG	1F		D00299	S/R			ALL
1011	20	X1	K		24-5	22-11-31	D04069P	A06			D00299	4			ALL
1011Z			K		0-0	22-11-31	D04069P	PERG	1F		D00299	S/R			ALL
1014	22	X1	AD		24-5	22-11-75	D00299	6			D04069P	A15			YD157-YR328
1014Z			AD		0-0	22-11-75	D00299	S/R			D04069P	PERG	1F		YD157-YR328
1015	22	X1	O		3-6	22-31-51	D00301	10			GD00981	DC..	E		ALL
1015Z			O		0-0	22-31-51	D00301	S/R			GD00977	ST..	E		ALL
1016	22	X1	P		24-5	22-14-11	D04069P	B11			D00301	15			ALL
1016Z			P		0-0	22-14-11	D04069P	PERG	1F		D00301	S/R			ALL
1017	22	X1	AI		24-5	22-11-11	D04069P	B02			D00299	34			ALL
1017Z			AI		0-0	22-11-11	D04069P	PERG	1F		D00299	S/R			ALL
1022	22	X1	AK		24-5	22-14-11	D04069P	B10			D00299	22			ALL
1022Z			AK		0-0	22-14-11	D04069P	PERG	1F		D00299	S/R			YC051-YD155
1022Z			AK		0-0	22-14-11	D04069P			AC	D00299	S/R			YD157-YR328
1023	22	X1	AL		24-5	22-11-11	D04069P	A04			D00299	23			ALL
1023Z			AL		0-0	22-11-11	D04069P	PERG	1F		D00299	S/R			ALL
1026	20	X1	BM		21-1	33-18-51	D00301	6			TB1806Y	B003	1A		ALL
1026Z			BM		0-0	33-18-51	D00301	S/R			GB01806	ST..	1A		ALL
1030	22	X1	BO		24-5	22-14-11	D04069P	A10			D00299	53			ALL

WIRE LIST

D280A108

91-21-11

Section W2360

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2363		286A2363			AUTO PILOT CONTROL PANEL SYSTEM A (continued)											
1030Z					BO	0-0	22-14-11	D04069P	PERG	1F		D00299	S/R			ALL
1045		22		X1	AW	24-5	22-11-11	D04069P	A02			D00299	45			ALL
1045Z					AW	0-0	22-11-11	D04069P	PERG	1F		D00299	S/R			ALL
1047		22		X1	AX	24-5	22-11-11	D04069P	A03			D00299	37			ALL
1047Z					AX	0-0	22-11-11	D04069P	PERG	1F		D00299	S/R			ALL
1062		20		X1	EE	12-11	33-11-31	D00299	14			SP00300		S		ALL
1062Z					EE	0-0	33-11-31	D00299	S/R			SP00300	REF		AD	ALL
1063		20		X1	BE	3-5	33-11-31	D00299	15			GD00541	AC..	E		ALL
1063Z					BE	0-0	33-11-31	D00299	S/R			GD00541	DED			ALL
1064		22		X1	BF	12-11	22-14-11	D00299	48			SP02135		S		ALL
1064Z					BF	0-0	22-14-11	D00299	S/R			SP02135	REF		AB	ALL
2001B		24		Y2	AA	24-5	31-62-11	D04069P	B14			D00299	35			ALL
2001R		24		Y2	AA	0-0	31-62-11	D04069P	B13			D00299	36			ALL
2001Z					AA	0-0	31-62-11	D04069P	PERG	1F		D00299	S/R			ALL
2003B		22		X2	AC	24-5	22-11-51	D00301	1			D04069P	B07			ALL
2003R		22		X2	AC	0-0	22-11-51	D00301	2			D04069P	A07			ALL
2003Z					AC	0-0	22-11-51	D00301	S/R			D04069P	PERG	1F		ALL
2013B		22		X2	AM	24-5	22-11-11	D04069P	B01			D00299	28			ALL
2013R		22		X2	AM	0-0	22-11-11	D04069P	A01			D00299	52			ALL
2013Z					AM	0-0	22-11-11	D04069P	PERG	1F		D00299	S/R			ALL
2015B		22		X2	AO	24-5	22-11-51	D04069P	B08			D00299	32			ALL
2015R		22		X2	AO	0-0	22-11-51	D04069P	A08			D00299	33			ALL
2015Z					AO	0-0	22-11-51	D04069P	PERG	1F		D00299	S/R			ALL
2017B		22		X2	AQ	24-5	22-11-51	D04069P	B09			D00299	17			ALL
2017R		22		X2	AQ	0-0	22-11-51	D04069P	A09			D00299	18			ALL
2017Z					AQ	0-0	22-11-51	D04069P	PERG	1F		D00299	S/R			ALL
3001B		20		X3	CA	24-5	22-11-12	D00299	3			D04069P	A05			ALL
3001R		20		X3	CA	0-0	22-11-12	D00299	54			D04069P	B04			ALL
3001Y		20		X3	CA	0-0	22-11-12	D00299	39			D04069P	B05			ALL
3001Z					CA	0-0	22-11-12	D00299	S/R			D04069P	PERG	1F		ALL
FRAC						0-0	22-14-11	D04069P			AC	D04069P	PERG	1F		YD157-YR328

WIRE LIST

D280A108

91-21-11

Section W2360

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2383	286A2383			RIGHT DC ELEX PWR FROM P6 TO E1 AND P9.											
0001	16		PA		9-6	31-62-21	D46065P				D46033P	15			YC051-YD157
0001	16		PA		9-7	31-62-21	D46065P				D46033P	15			YD158-YR328
0002	16		PA		9-6	31-62-21	D46065P				D46033P	19			YC051-YD157
0002	16		PA		9-7	31-62-21	D46065P				D46033P	19			YD158-YR328
0003	20		CQ		13-5	22-18-11	D46065P				D46023P	A03			YC051-YD157
0003	20		CQ		13-6	22-18-11	D46065P				D46023P	A03			YD158-YR328
0004	20		CQ		11-11	22-11-12	D46065P				D46031J	4			YC051-YD155
0004	20		CQ		11-11	22-11-12	D46065P				D46031J	1			YD157
0004	20		CQ		12-0	22-11-12	D46065P				D46031J	1			YD158-YR328
0005	22		PA		13-5	34-51-41	D46065P				D46023P	A04			YC051-YD157
0005	22		PA		13-6	34-51-41	D46065P				D46023P	A04			YD158-YR328
0006	24		PK		9-6	32-42-11	D46065P				D46033P	6			YC051-YD157
0006	24		PK		9-7	32-42-11	D46065P				D46033P	6			YD158-YR328
0007	20		CQ		13-5	34-21-21	D46065P				D46023P	A07			YC051-YD157
0007	20		CQ		13-6	34-21-21	D46065P				D46023P	A07			YD158-YR328
0008	20		PA		9-6	33-14-11	D46065P				D46033P	8			YC051-YD157
0008	20		PA		9-7	33-14-11	D46065P				D46033P	8			YD158-YR328
0009	24		PK		11-11	SPARE	D46065P				D46031J	9			YC051-YD157
0009	24		PK		12-0	SPARE	D46065P				D46031J	9			YD158-YR328
0010	16		PA		9-6	31-62-21	D46065P				D46033P	23			YC051-YD157
0010	16		PA		9-7	31-62-21	D46065P				D46033P	23			YD158-YR328
0012	20		CQ		11-11	22-11-12	D46065P				D46031J	2			YC051-YD157
0012	20		CQ		12-0	22-11-12	D46065P				D46031J	2			YD158-YR328
0013	20		CQ		11-11	22-11-11	D46065P				D46031J	3			YC051-YD157
0013	20		CQ		12-0	22-11-11	D46065P				D46031J	3			YD158-YR328
0014	18		PA		13-5	22-31-11	D46065P				D46023P	H			YC051-YD155
0015	24		PK		9-6	SPARE	D46065P				D46033P	5			YC051-YD157
0015	24		PK		9-7	SPARE	D46065P				D46033P	5			YD158-YR328
0016	16		PA		13-5	23-12-21	D46065P				D46023P	J			YC051-YD157
0016	16		PA		7-1	23-12-21	D46065P				SP00167		9		YD158-YR328
0017	16		PA		9-6	33-11-21	D46065P		16		D46033P	27			YC051-YD157
0017	16		PA		9-7	33-11-21	D46065P		16		D46033P	27			YD158-YR328
0018	16		PA		13-5	23-12-21	D46065P				D46023P	K			YC051-YD157
0018	16		PA		13-6	SPARE	D46065P				D46023P	K			YL951-YL999, YN501-YR328
0019	20		PA		9-6	SPARE	D46065P				D46033P	9			YC051-YD157
0019	20		PA		9-7	SPARE	D46065P				D46033P	9			YD158-YR328
0020	20		PA		9-6	33-18-21	D46065P				D46033P	10			YC051-YD157
0020	20		PA		9-7	33-18-21	D46065P				D46033P	10			YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W2380

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2383		286A2383			RIGHT DC ELEX PWR FROM P6 TO E1 AND P9. (continued)											
0021		22		PA		13-5	27-81-11	D46065P		21		D46023P		A01		YC051-YD157
0021		22		PA		13-6	27-81-11	D46065P		21		D46023P		A01		YD158-YR328
0022		24		PK		13-5	27-28-11	D46065P		22		D46023P		A02		YC051-YD157
0022		24		PK		13-6	27-28-11	D46065P		22		D46023P		A02		YD158-YR328
0023		20		PA		13-5	SPARE	D46065P		23		D46023P		A05		YC051-YD157
0023		20		PA		13-6	SPARE	D46065P		23		D46023P		A05		YD158-YR328
0024		20		PA		11-11	SPARE	D46065P		24		D46031J		8		YC051-YD157
0024		20		PA		12-0	SPARE	D46065P		24		D46031J		8		YD158-YR328
0025		20		PA		11-11	SPARE	D46065P		25		D46031J		5		YC051-YD155
0025		20		PA		11-11	22-11-12	D46065P		25		D46031J		5		YD157
0025		20		PA		12-0	22-11-12	D46065P		25		D46031J		5		YD158-YR328
0026		22		PA		11-11	SPARE	D46065P		26		D46031J		6		YC051-YD157
0026		22		PA		12-0	SPARE	D46065P		26		D46031J		6		YD158-YR328
0027		22		PA		11-11	SPARE	D46065P		27		D46031J		7		YC051-YD155
0028		20		CQ		13-5	34-21-21	D46065P		28		D46023P		A06		YC051-YD157
0028		20		CQ		13-6	34-21-21	D46065P		28		D46023P		A06		YD158-YR328
0029		22		PA		9-6	31-62-21	D46065P		29		D46033P		12		YC051-YD157
0029		22		PA		9-7	31-62-21	D46065P		29		D46033P		12		YD158-YR328
0030		20		CQ		9-6	33-14-11	D46065P		30		D46033P		13		YC051-YD157
0030		20		CQ		9-7	33-14-11	D46065P		30		D46033P		13		YD158-YR328
0031		20		PA		9-6	SPARE	D46065P		31		D46033P		1		YC051-YD157
0031		20		PA		9-7	SPARE	D46065P		31		D46033P		1		YD158-YR328
0032		20		PA		9-6	SPARE	D46065P		32		D46033P		2		YC051-YD155
0033		16		PA		8-7	33-11-21	D46033P		18	16	SP02140			S	ALL
0034		16		PA		14-11	33-11-21	D46033P		26	16	TB0805V		A005	1	YC051-YD157
0034		16		PA		15-0	33-11-21	D46033P		26	16	TB0805V		A005	1	YD158-YR328
0035		20		PA		7-10	SPARE	D46033P		11		SP02141			S	YD158-YD170
0036		16		PA		10-6	23-12-21	D46023P		J		SP00167			9	YD158-YR328
0038		18		PA		11-11	22-11-11	D46065P		4		D46031J		10		YD157
0038		18		PA		12-0	22-11-11	D46065P		4		D46031J		10		YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W2380

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To					
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
I	W2401	286A2401			SELCAL CONTROL PANEL(P8) TO E/E BAY											
I	0001	24		PK		32-3	23-22-11	D00551		L		D04721P	A01			YD158-YR328
I	0002	24		PK		32-3	23-22-11	D00551		M		D04721P	A02			YD158-YR328
I	0003	24		PK		32-3	23-22-11	D00551		N		D04721P	A03			YD158-YR328
I	0004	24		PK		32-3	23-22-11	D00551		P		D04721P	A04			YD158-YR328
I	0005	24		PK		32-3	23-22-11	D00551		R		D04721P	A05			YD158-YR328
I	0006	24		PK		32-3	23-22-11	D00551		D		D04721P	A06			YD158-YR328
I	0007	24		PK		32-3	23-22-11	D00551		E		D04721P	A07			YD158-YR328
I	0008	24		PK		32-3	23-22-11	D00551		F		D04721P	A08			YD158-YR328
I	0009	24		PK		32-3	23-22-11	D00551		G		D04721P	A09			YD158-YR328
I	0010	24		PK		32-3	23-22-11	D00551		H		D04721P	A10			YD158-YR328
I	0012	22		PA		3-7	23-22-11	D00551		S		GD00801	DC..	1A		YD158-YN235
I	0012	22		PA		3-7	23-22-11	D00551		S		GD00801	ST..	1A		YN236-YR328
I	0013	20		CQ		4-2	33-11-41	D00551		U		TB0801W	A013	1		YD158-YR328
I	0014	20		CQ		3-11	33-11-41	D00551		V		GD00805	AC..	1A		YD158-YR328
I	0015	20		CQ		4-2	33-18-61	D00551		B		TB0803Y	A013	1A		YD158-YR328
I	0016	20		CQ		4-7	33-18-61	D00551		C		TB0804Z	A017	1A		YD158-YR328
I	0020	24		PK		32-3	SPARE	D00551		T		D04721P	B10			YD158-YR328
I	W2403	286A2403			VHF COMM NO. 1 CONTROL PNL											
I	0001	20		CQ		4-0	33-11-33	D00203		1		TB0801W	B021	1		YC051-YC068
I	0001	20		CQ		4-5	33-11-33	D00203		1		TB0801W	B021	1		YC070-YD157
I	0002	20		CQ		3-11	33-11-33	D00203		2		GD00805	AC..	1A		YC051-YC068
I	0002	20		CQ		4-1	33-11-33	D00203		2		GD00805	AC..	1A		YC070-YD157
I	0004	22		PA		14-3	23-12-11	D00203		4		D04123P		4		YC051-YC068
I	0004	22		PA		14-8	23-12-11	D00203		4		D04123P		4		YC070-YD157
I	0010	20		PA		14-1	23-12-11	D00203		20		D04123P		10		YC051-YC068
I	0010	20		PA		14-8	23-12-11	D00203		20		D04123P		10		YC070-YD157
I	0012	22		PA		4-3	23-12-11	D00203		12		GD00801	ST..	1A		YC051-YC068
I	0012	22		PA		3-8	23-12-11	D00203		12		GD00801	ST..	1A		YC070-YD157
I	0013	18		PA		14-1	23-12-11	D00203		13	18	D04123P		7		YC051-YC068
I	0013	18		PA		14-8	23-12-11	D00203		13	18	D04123P		7		YC070-YD157
I	0014	20		PA		4-3	23-12-11	D00203		14		GD00801	DC..	1A		YC051-YC068
I	0014	20		PA		3-8	23-12-11	D00203		14		GD00801	DC..	1A		YC070-YD157
I	0023	20		CQ		7-8	33-18-62	D00203		23		TB0804Z	A017	1A		YC051-YC064, YC067-YC068
I	0023	20		CQ		7-8	33-18-62	D00203		23		SP00321		9		YC065
I	0023	20		CQ		6-2	33-18-62	D00203		23		SP00321		9		YC070-YD157
I	2001B	24		PL	AA	14-3	23-12-11	D00203		CAP	Y	D04123P		12		YC051-YC068
I	2001B	24		PL	AA	14-10	23-12-11	D00203		CAP	Y	D04123P		12		YC070-YD157

WIRE LIST

D280A108

91-21-11

Section W2400

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Diagram	From					To					Effectivity
	Wire No.	GA	CO TY			Fam	FT-IN	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W2403	286A2403			VHF COMM NO. 1 CONTROL PNL (continued)												
2001R	24	PL	AA		0-0	23-12-11	D00203		CAP	Y		D04123P	11			YC051-YD157
2002B	24	Y2	AB		14-1	23-12-11	D00203		22			D04123P	2			YC051-YC068
2002B	24	Y2	AB		14-8	23-12-11	D00203		22			D04123P	2			YC070-YD157
2002R	24	Y2	AB		0-0	23-12-11	D00203		21			D04123P	1			YC051-YD157
2002Z			AB		0-0	23-12-11	D00203		19			D04123P	3			YC051-YD157
W2405	286A2405			VHF COMM NO.2 CONTROL PNL												
0001	20	CQ			3-10	33-11-41	D00209		1			TB0801W	A021	1		YC051-YD157
0002	20	CQ			3-9	33-11-41	D00209		2			GD00805	AC..	1A		YC051-YD157
0004	22	PA			15-0	23-12-21	D00209		4			D04125J	4			YC051-YD157
0010	20	PA			14-10	23-12-21	D00209		20			D04125J	10			YC051-YD157
0012	22	PA			3-10	23-12-21	D00209		12			GD00809	ST..	1A		YC051-YD157
0013	18	PA			14-10	23-12-21	D00209		13	18		D04125J	7			YC051-YD157
0014	20	PA			3-10	23-12-21	D00209		14			GD00809	DC..	1A		YC051-YD157
0023	20	CQ			6-4	33-18-62	D00209		23			TB0804Z	A017	1A		YC051-YD157
2001B	24	PL	AA		15-0	23-12-21	D00209		CAP	Y		D04125J	12			YC051-YD157
2001R	24	PL	AA		0-0	23-12-21	D00209		CAP	Y		D04125J	11			YC051-YD157
2002B	24	Y2	AB		14-10	23-12-21	D00209		22			D04125J	2			YC051-YD157
2002R	24	Y2	AB		0-0	23-12-21	D00209		21			D04125J	1			YC051-YD157
2002Z			AB		0-0	23-12-21	D00209		19			D04125J	S/R			YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W2400

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		Diagram	From			To					
	Wire No.	GA	CO TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2413	286A2413			RADIO TUNING PANEL 1 (P8-71) TO E3-3												
0001	20		PA		5-0	23-12-11		D00203		1		GD00801	ST..	1A		YD158-YR328
0004	24		PK		33-8	23-12-41		D00203		4		D43363P	A04			YD158-YR328
0007	20		PA		4-7	23-12-11		D10601		21		GD00801	DC..	1A		YL951-YR328
0010	22		PA		33-8	23-12-11		D00203		10		D43363P	B04			YD158-YR328
0011	22		CQ		33-8	23-12-31		D00203		11		D43363P	A07			YD158-YR328
0012	22		CQ		33-8	23-12-21		D00203		12		D43363P	B07			YD158-YR328
0019	22		PA		5-0	23-12-11		D00203		19	VP	GD00801	DC..	1A		YD158-YD170
0021	24		PK		33-8	23-11-16		D00203		21		D43363P	A05			YD158-YD170
0022	24		PK		33-8	23-11-26		D00203		22		D43363P	B06			YD158-YD170
0026	22		PA		33-8	23-11-11		D00203		26		D43363P	B05			YD158-YR328
0029	22		PA		33-8	23-11-11		D00203		29		D43363P	A06			YD158-YR328
0030	24		PK		0-7	23-12-11		D00203		23		D00203	30			YD158-YR328
0035	20		CQ		7-2	33-18-62		D00203		35		SP00321		9		YD158-YR328
0036	20		CQ		6-2	33-18-62		D00203		36		TB0804Y	A007	1A		YD158-YR328
0037	20		CQ		6-3	33-11-33		D00203		37		TB0801W	B021	1		YD158-YR328
0038	20		CQ		5-3	33-11-33		D00203		38		GD00805	AC..	1A		YD158-YR328
0040	18		CQ		9-5	23-12-11		D00203		40	18	SP00165		S		YD158-YR328
0041	20		CQ		5-0	23-12-11		D00203		41		GD00801	DC..	1A		YD158-YR328
0054	24		PK		9-5	23-27-31		D00203		14		SP00087		S		YD158-YR328
0055	24		PK		9-5	23-27-31		D00203		15	VP	SP00083		S		YL951-YR328
0059	24		PK		9-5	23-27-31		D00203		19	VP	SP00081		S		YL951-YR328
0110	22		PA		5-0	23-12-41		D00203		28		GD00801	DC..	1A		YL951-YL954, YN231-YN235
2501B	24		Y2	AA	33-8	23-12-41		D00203		3		D43363P	B01			YD158-YR328
2501R	24		Y2	AA	0-0	23-12-41		D00203		2		D43363P	A01			YD158-YR328
2501Z				AA	0-0	23-12-41		D00203		DED		D43363P	PERG	1F		YD158-YR328
2502B	24		Y2	AB	33-3	23-12-11		D10601		2		D43365P	B01			YD158-YR328
2502R	24		Y2	AB	0-0	23-12-11		D10601		1		D43365P	A01			YD158-YR328
2502Z				AB	0-0	23-12-11		D10601		DED		D43365P	PERG	1F		YD158-YR328
2503B	24		Y2	AC	33-3	23-11-11		D10601		18		D43365P	B02			YD158-YR328
2503R	24		Y2	AC	0-0	23-11-11		D10601		17		D43365P	A02			YD158-YR328
2503Z				AC	0-0	23-11-11		D10601		DED		D43365P	PERG	1F		YD158-YR328
2504B	24		Y2	AD	33-3	23-11-21		D10601		23		D43365P	B03			YD158-YR328
2504R	24		Y2	AD	0-0	23-11-21		D10601		22		D43365P	A03			YD158-YR328
2504Z				AD	0-0	23-11-21		D10601		DED		D43365P	PERG	1F		YD158-YR328
2505B	24		Y2	AE	33-8	23-12-41		D00203		9		D43363P	B02			YD158-YR328
2505R	24		Y2	AE	0-0	23-12-41		D00203		8		D43363P	A02			YD158-YR328
2505Z				AE	0-0	23-12-41		D00203		DED		D43363P	PERG	1F		YD158-YR328
2506B	24		Y2	AF	33-3	23-12-21		D10601		10		D43365P	B04			YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W2410

Page 1

Nov 12/2012



WIRE LIST

91-21-11

Section W2410

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W2415	286A2415				RADIO TUNING PNL 2 TO E3-3 (continued)											
0110	22		PA		4-11	23-12-41		D00209	28			GD00809	DC..	1A		YL951-YL954, YN231-YN235
2501B	24		Y2	AA	30-9	23-12-41		D00209	3			D43355P	B01			YD158-YD170
2501B	24		Y2	AA	31-3	23-12-41		D00209	3			D43355P	B01			YL951-YR328
2501R	24		Y2	AA	0-0	23-12-41		D00209	2			D43355P	A01			YD158-YR328
2501Z				AA	0-0	23-12-41		D00209	DED			D43355P	PERG	1F		YD158-YR328
2502B	24		Y2	AB	30-8	23-12-21		D10603	10			D43357P	B01			YD158-YD170
2502B	24		Y2	AB	31-3	23-12-21		D10603	10			D43357P	B01			YL951-YR328
2502R	24		Y2	AB	0-0	23-12-21		D10603	9			D43357P	A01			YD158-YR328
2502Z				AB	0-0	23-12-21		D10603	DED			D43357P	PERG	1F		YD158-YR328
2503B	24		Y2	AC	30-8	23-11-11		D10603	18			D43357P	B02			YD158-YD170
2503B	24		Y2	AC	31-3	23-11-11		D10603	18			D43357P	B02			YL951-YR328
2503R	24		Y2	AC	0-0	23-11-11		D10603	17			D43357P	A02			YD158-YR328
2503Z				AC	0-0	23-11-11		D10603	DED			D43357P	PERG	1F		YD158-YR328
2504B	24		Y2	AD	30-8	23-11-21		D10603	23			D43357P	B03			YD158-YD170
2504B	24		Y2	AD	31-3	23-11-21		D10603	23			D43357P	B03			YL951-YR328
2504R	24		Y2	AD	0-0	23-11-21		D10603	22			D43357P	A03			YD158-YR328
2504Z				AD	0-0	23-11-21		D10603	DED			D43357P	PERG	1F		YD158-YR328
2505B	24		Y2	AE	30-9	23-12-41		D00209	6			D43355P	B02			YD158-YD170
2505B	24		Y2	AE	31-3	23-12-41		D00209	6			D43355P	B02			YL951-YR328
2505R	24		Y2	AE	0-0	23-12-41		D00209	5			D43355P	A02			YD158-YR328
2505Z				AE	0-0	23-12-41		D00209	DED			D43355P	PERG	1F		YD158-YR328
2506B	24		Y2	AF	30-8	23-12-11		D10603	2			D43357P	B04			YD158-YD170
2506B	24		Y2	AF	31-3	23-12-11		D10603	2			D43357P	B04			YL951-YR328
2506R	24		Y2	AF	0-0	23-12-11		D10603	1			D43357P	A04			YD158-YR328
2506Z				AF	0-0	23-12-11		D10603	DED			D43357P	PERG	1F		YD158-YR328
2507B	24		Y2	AG	30-8	23-12-31		D10603	14			D43357P	B05			YD158-YD170
2507B	24		Y2	AG	31-3	23-12-31		D10603	14			D43357P	B05			YL951-YR328
2507R	24		Y2	AG	0-0	23-12-31		D10603	13			D43357P	A05			YD158-YR328
2507Z				AG	0-0	23-12-31		D10603	DED			D43357P	PERG	1F		YD158-YR328
2508B	24		Y2	AH	30-9	23-12-41		D00209	9			D43355P	B03			YD158-YD170
2508B	24		Y2	AH	31-3	23-12-41		D00209	9			D43355P	B03			YL951-YR328
2508R	24		Y2	AH	0-0	23-12-41		D00209	8			D43355P	A03			YD158-YR328
2508Z				AH	0-0	23-12-41		D00209	DED			D43355P	PERG	1F		YD158-YR328
W2417	286A2417				RADIO TUNING PNL 3 TO E3-3											
0001	20		PA		4-0	23-12-31		D00549	1			GD00807	ST..	1A		YD158-YR328
0003	20		PA		4-2	23-12-31		D10605	21			GD00807	DC..	1A		YL951-YN260
0007	20		PA		4-2	23-12-31		D10605	21			GD00807	DC..	1A		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W2410

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice		
W2417	286A2417				RADIO TUNING PNL 3 TO E3-3 (continued)											
0010	22		CQ		28-11	23-12-11		D00549	10			D43329P	A08			YD158-YR328
0011	22		PA		28-11	23-12-31		D00549	11			D43329P	B06			YD158-YR328
0012	22		CQ		28-11	23-12-21		D00549	12			D43329P	B08			YD158-YR328
0013	24		PK		8-5	MULTI		D00549	13			SP00081		S		YL951-YL954, YN231-YN235
0013	24		PK		8-5	SPARE		D00549	13			SP00081		S		YN501-YR328
0015	22		PA		4-0	23-12-31		D00549	REF	VP		GD00807	DC..	1A		YD158-YD170
0021	24		PK		28-11	23-11-16		D00549	21			D43329P	A06			YD158-YD170
0022	24		PK		28-11	23-11-26		D00549	22			D43329P	B07			YD158-YD170
0023	24		PK		0-7	23-12-31		D00549	23			SM00001		W		YD158-YR328
0030	24		PK		0-7	23-12-31		D00549	30			SM00001		W		YD158-YR328
0031	24		PK		0-7	23-12-31		D00549	31			SM00001		W		YD158-YR328
0035	20		CQ		4-7	33-18-62		D00549	35			TB0804Z	A017	1A		YD158-YR328
0036	20		CQ		4-4	33-18-62		D00549	36			TB0804Y	B005	1A		YD158-YR328
0037	20		CQ		4-2	33-11-41		D00549	37			TB0801W	A013	1		YD158-YD170
0037	20		G5		4-2	33-11-41		D00549	37			TB0801W	A013	1		YL951-YR328
0038	20		CQ		4-0	33-11-41		D00549	38			GD00807	AC..	1A		YD158-YD170
0038	20		G5		4-0	33-11-41		D00549	38			GD00807	AC..	1A		YL951-YR328
0040	18		CQ		28-11	23-12-31		D00549	40	18		D43329P	F			YD158-YD170
0040	18		PA		28-11	23-12-31		D00549	40	18		D43329P	F			YL951-YR328
0041	20		PA		4-0	23-12-31		D00549	41			GD00807	DC..	1A		YD158-YR328
0054	24		PK		8-5	23-27-31		D00549	14			SP00087		S		YD158-YD170
0054	24		B6		8-5	23-27-31		D00549	14			SP00087		S		YL951-YR328
0055	24		B6		8-5	23-27-31		D00549	15	VP		SP00083		S		YL951-YR328
0059	24		B6		8-5	23-27-31		D00549	19	VP		SP00081		S		YL951-YR328
0110	22		PA		4-0	23-12-41		D00549	28			GD00807	DC..	1A		YL951-YL954, YN231-YN235
2501B	24		Y2	AA	28-11	23-12-41		D00549	3			D43329P	B03			YD158-YR328
2501R	24		Y2	AA	0-0	23-12-41		D00549	2			D43329P	A03			YD158-YR328
2501Z				AA	0-0	23-12-41		D00549	DED			D43329P	PERG	1F		YD158-YR328
2502B	24		Y2	AB	28-7	23-12-31		D10605	14			D43391P	B01			YD158-YD170
2502B	24		Y2	AB	28-8	23-12-31		D10605	14			D43391P	B01			YL951-YR328
2502R	24		Y2	AB	0-0	23-12-31		D10605	13			D43391P	A01			YD158-YR328
2502Z				AB	0-0	23-12-31		D10605	DED			D43391P	PERG	1F		YD158-YR328
2503B	24		Y2	AC	28-7	23-11-11		D10605	18			D43391P	B02			YD158-YD170
2503B	24		Y2	AC	28-8	23-11-11		D10605	18			D43391P	B02			YL951-YR328
2503R	24		Y2	AC	0-0	23-11-11		D10605	17			D43391P	A02			YD158-YR328
2503Z				AC	0-0	23-11-11		D10605	DED			D43391P	PERG	1F		YD158-YR328
2504B	24		Y2	AD	28-7	23-11-21		D10605	23			D43391P	B03			YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W2410

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2417	286A2417				RADIO TUNING PNL 3 TO E3-3 (continued)										
2504B	24	Y2	AD		28-8	23-11-21	D10605	23			D43391P	B03			YL951-YR328
2504R	24	Y2	AD		0-0	23-11-21	D10605	22			D43391P	A03			YD158-YR328
2504Z			AD		0-0	23-11-21	D10605	DED			D43391P	PERG	1F		YD158-YR328
2505B	24	Y2	AE		28-7	23-12-11	D10605	2			D43391P	B04			YD158-YD170
2505B	24	Y2	AE		28-8	23-12-11	D10605	2			D43391P	B04			YL951-YR328
2505R	24	Y2	AE		0-0	23-12-11	D10605	1			D43391P	A04			YD158-YR328
2505Z			AE		0-0	23-12-11	D10605	DED			D43391P	PERG	1F		YD158-YR328
2506B	24	Y2	AF		28-11	23-12-41	D00549	9			D43329P	B04			YD158-YR328
2506R	24	Y2	AF		0-0	23-12-41	D00549	8			D43329P	A04			YD158-YR328
2506Z			AF		0-0	23-12-41	D00549	DED			D43329P	PERG	1F		YD158-YR328
2507B	24	Y2	AG		28-7	23-12-21	D10605	10			D43391P	B05			YD158-YD170
2507B	24	Y2	AG		28-8	23-12-21	D10605	10			D43391P	B05			YL951-YR328
2507R	24	Y2	AG		0-0	23-12-21	D10605	9			D43391P	A05			YD158-YR328
2507Z			AG		0-0	23-12-21	D10605	DED			D43391P	PERG	1F		YD158-YR328
2508B	24	Y2	AH		28-11	23-12-41	D00549	6			D43329P	B05			YD158-YR328
2508R	24	Y2	AH		0-0	23-12-41	D00549	5			D43329P	A05			YD158-YR328
2508Z			AH		0-0	23-12-41	D00549	DED			D43329P	PERG	1F		YD158-YR328
W2419	286A2419				FLIGHT RECORDER E3-2 SHELF TO TEST CONNECTOR										
0001	22	PA			12-10	31-31-11	D01637	2			TB1808Y	B009	1A		ALL
0002	22	PA			12-10	31-31-11	D01637	1			TB1808Y	B009	1A		ALL
0003	22	PA			26-3	31-31-11	D01637	11			D43219P	A07			YC051-YC055
0003	22	PA			27-1	31-31-11	D01637	11			D43219P	A07			YC056-YR328
0004	22	PA			26-3	31-31-11	D01637	10			D43219P	A08			YC051-YC055
0004	22	PA			27-1	31-31-11	D01637	10			D43219P	A08			YC056-YR328
2001B	24	Y2	AA		26-3	31-31-11	D01637	9			D43219P	A04			YC051-YC055
2001B	24	Y2	AA		27-1	31-31-11	D01637	9			D43219P	A04			YC056-YR328
2001R	24	Y2	AA		0-0	31-31-11	D01637	8			D43219P	A03			ALL
2001Z			AA		0-0	31-31-11	D01637			FA	D43219P	PERG	1F		ALL
2002B	24	Y2	AB		26-3	31-31-11	D01637	5			D43219P	A06			YC051-YC055
2002B	24	Y2	AB		27-1	31-31-11	D01637	5			D43219P	A06			YC056-YR328
2002R	24	Y2	AB		0-0	31-31-11	D01637	4			D43219P	A05			ALL
2002Z			AB		0-0	31-31-11	D01637			FA	D43219P	PERG	1F		ALL
FRAA					0-0	31-31-11	D01637			FA	D01637		3		ALL

WIRE LIST

D280A108

91-21-11
Section W2410
Page 5 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2465		286A2465					AUTOPILOT CONTROL PANEL SYSTEM - B									
1001		20		VF	A	3-3	22-11-11	D01815		1		GD00985	DC..	E	*	ALL
1001Z					A	0-0	22-11-11	D01815		S/R		GD00980	ST..	E	*1	ALL
1002		22		X1	B	22-5	22-11-75	D08019J		25		D01815	53			YD157-YR328
1002Z					B	0-0	22-11-75	D08019J		S/R		D01815	S/R			YD157-YR328
1003		20		VF	C	22-5	22-11-12	D08019J		3		D01815	3			ALL
1003Z					C	0-0	22-11-12	D08019J		S/R		D01815	S/R			ALL
1004		20		X1	D	22-5	22-11-31	D08019J		4		D01815	4			ALL
1004Z					D	0-0	22-11-31	D08019J		S/R		D01815	S/R			ALL
1005		20		X1	E	3-3	22-11-11	D01815		5		GD00985	DC..	E	*	ALL
1005Z					E	0-0	22-11-11	D01815		S/R		GD00980	ST..	E	*1	ALL
1016		20		X1	P	22-5	22-12-41	D08019J		16		D01815	16			ALL
1016Z					P	0-0	22-12-41	D08019J		S/R		D01815	S/R			ALL
1020		22		X1	F	22-5	22-14-11	D08019J		10		D01815	15			YD157-YR328
1020Z					F	0-0	22-14-11	D08019J		S/R		D01815	S/R			YD157-YR328
1022		22		X1	W	22-5	22-14-11	D08019J		22		D01815	22			ALL
1022Z					W	0-0	22-14-11	D08019J		S/R		D01815	S/R			ALL
1023		22		X1	X	22-5	22-11-11	D08019J		23		D01815	23			ALL
1023Z					X	0-0	22-11-11	D08019J		S/R		D01815	S/R			ALL
1025		22		X1	Z	22-5	22-14-11	D08019J		5		D01815	25			ALL
1025Z					Z	0-0	22-14-11	D08019J		S/R		D01815	S/R			ALL
1034		22		X1	AQ	22-5	22-11-11	D08019J		14		D01815	34			ALL
1034Z					AQ	0-0	22-11-11	D08019J		S/R		D01815	S/R			ALL
1037		22		X1	AS	22-5	22-11-11	D08019J		7		D01815	37			ALL
1037Z					AS	0-0	22-11-11	D08019J		S/R		D01815	S/R			ALL
1039		20		X1	AT	22-5	22-11-12	D08019J		9		D01815	39			ALL
1039Z					AT	0-0	22-11-12	D08019J		S/R		D01815	S/R			ALL
1043		22		X1	AV	22-5	22-11-11	D08019J		6		D01815	43			ALL
1043Z					AV	0-0	22-11-11	D08019J		S/R		D01815	S/R			ALL
1045		22		X1	AW	22-5	22-11-11	D08019J		15		D01815	45			ALL
1045Z					AW	0-0	22-11-11	D08019J		S/R		D01815	S/R			ALL
1047		20		X1	AX	3-3	22-11-11	D01815		47		GD00985	DC..	E	*	ALL
1047Z					AX	0-0	22-11-11	D01815		S/R		GD00980	ST..	E	*1	ALL
1054		20		X1	BA	22-5	22-11-12	D08019J		24		D01815	54			ALL
1054Z					BA	0-0	22-11-12	D08019J		S/R		D01815	S/R			ALL
1055		20		X1	BB	3-3	22-11-11	D01815		55		GD00985	DC..	E	*	ALL
1055Z					BB	0-0	22-11-11	D01815		S/R		GD00980	ST..	E	*1	ALL
2005B		24		Y2	AE	22-5	31-62-21	D08019J		20		D01815	20			ALL
2005R		24		Y2	AE	0-0	31-62-21	D08019J		21		D01815	21			ALL
2005Z					AE	0-0	31-62-21	D08019J		S/R		D01815	S/R			ALL

WIRE LIST

D280A108

91-21-11

Section W2460

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
	Wire No.	GA	CO	TY	Fam	FT-IN	Diagram								
W2465		286A2465					AUTOPILOT CONTROL PANEL SYSTEM - B (continued)								
	2018B	22	X2	R		22-5	22-11-51	D08019J		19	D01815		17		ALL
	2018R	22	X2	R		0-0	22-11-51	D08019J		18	D01815		18		ALL
	2018Z			R		0-0	22-11-51	D08019J		S/R	D01815		S/R		ALL
	2033B	22	X2	CK		22-5	22-11-51	D08019J		13	D01815		32		ALL
	2033R	22	X2	CK		0-0	22-11-51	D08019J		12	D01815		33		ALL
	2033Z			CK		0-0	22-11-51	D08019J		S/R	D01815		S/R		ALL
	2052B	22	X2	AC		22-5	22-11-11	D08019J		2	D01815		28		ALL
	2052R	22	X2	AC		0-0	22-11-11	D08019J		1	D01815		52		ALL
	2052Z			AC		0-0	22-11-11	D08019J		S/R	D01815		S/R		ALL

WIRE LIST

D280A108

91-21-11

Section W2460

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W2508	286A2508			P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2										
0002	22	PA		7-5	23-42-11	L00019	1	B		TB0506Y	B005	1A	YD158, YL951-YR328	
0003	24	PK		29-3	52-71-12	D00482	12			D46108P	23		YC051-YC052	
0003	24	PK		29-2	52-71-12	D00482	12			D46108P	23		YC053-YC055, YC059-YD158, YL951-YR328	
0003	24	PK		29-4	52-71-12	D00482	12			D46108P	23		YC056-YC058	
0006	20	CQ		29-2	52-71-13	D01406	10			D46108P	27		YC051-YC052	
0006	20	CQ		29-1	52-71-13	D01406	10			D46108P	27		YC053-YC058, YC065-YD158, YL951-YR328	
0006	20	CQ		29-0	52-71-13	D01406	10			D46108P	27		YC059-YC064	
0007	20	CQ		29-2	52-71-14	D01406	7			D46108P	29		YC051-YC052	
0007	20	CQ		29-1	52-71-14	D01406	7			D46108P	29		YC053-YC058, YC065-YD158, YL951-YR328	
0007	20	CQ		29-0	52-71-14	D01406	7			D46108P	29		YC059-YC064	
0008	20	CQ		29-3	52-71-13	D00482	4			D46108P	26		YC051-YC052	
0008	20	CQ		29-2	52-71-13	D00482	4			D46108P	26		YC053-YC055, YC059-YD158, YL951-YL999, YR301-YR328	
0008	20	CQ		29-4	52-71-13	D00482	4			D46108P	26		YC056-YC058	
0009	20	CQ		29-3	52-71-14	D00482	11			D46108P	28		YC051-YC052	
0009	20	CQ		29-2	52-71-14	D00482	11			D46108P	28		YC053-YC055, YC059-YD158, YL951-YL999, YR301-YR328	
0009	20	CQ		29-4	52-71-14	D00482	11			D46108P	28		YC056-YC058	
0024	24	B6		37-9	34-24-15	D00652	44			D40554P	A01		YD158, YL951-YR328	
0025	20	CQ		2-5	34-24-15	D00652	45			GD00519	DC..	1A	YD158, YL951-YR328	
0030	22	CQ		10-0	21-33-11	TB0502Y	B009	1A		D00654	8		YC060-YC064	
0030	22	CQ		6-6	21-33-11	D00654	8			TB0502Y	B009	1A	YL952-YL999, YN232-YR328	
0502	24	B6		6-7	24-31-11	D10596	32			D40550P	35		YC051-YC052	
0502	24	B6		8-9	24-31-11	D10596	32			D40550P	35		YC053-YC058	
0502	24	B6		9-0	24-31-11	D10596	32			D40550P	35		YC059-YC064	
0502	24	B6		6-11	24-31-11	D10596	32			D40550P	35		YC065-YD158, YL951-YR328	
0504	20	PA		3-11	24-32-11	D00730	23			GD00503	DC..	1A	YC051-YC058	

WIRE LIST

D280A108

91-21-11

Section W2500

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type
W2508	286A2508			P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)										
0504	20	PA		3-7	24-32-11	D00730		23		GD00503	DC..	1A		YC059-YD158, YL951-YR328
0505	24	PK		3-10	24-32-11	D00730		24		D10596	31			YC051-YC052
0505	24	PK		2-9	24-32-11	D00730		24		D10596	31			YC053-YC058
0505	24	PK		2-11	24-32-11	D00730		24		D10596	31			YC059-YD158, YL951-YR328
0506	24	PK		8-0	24-32-11	D00730		11		D40550P	39			YC051-YC052
0506	24	PK		10-3	24-32-11	D00730		11		D40550P	39			YC053-YC058
0506	24	PK		10-2	24-32-11	D00730		11		D40550P	39			YC059-YC064
0506	24	PK		8-1	24-32-11	D00730		11		D40550P	39			YC065-YD158, YL951-YR328
0509	24	B6		6-7	24-33-11	D00652		25		D40550P	53			YC051-YC052
0509	24	B6		8-10	24-33-11	D00652		25		D40550P	53			YC053-YC055
0509	24	B6		8-11	24-33-11	D00652		25		D40550P	53			YC056-YC058
0509	24	B6		9-0	24-33-11	D00652		25		D40550P	53			YC059-YC064
0509	24	B6		6-11	24-33-11	D00652		25		D40550P	53			YC065-YD158, YL951-YR328
0510	24	B6		6-7	24-33-11	D00652		43		D40550P	55			YC051-YC052
0510	24	B6		8-10	24-33-11	D00652		43		D40550P	55			YC053-YC055
0510	24	B6		8-11	24-33-11	D00652		43		D40550P	55			YC056-YC058
0510	24	B6		9-0	24-33-11	D00652		43		D40550P	55			YC059-YC064
0510	24	B6		6-11	24-33-11	D00652		43		D40550P	55			YC065-YD158, YL951-YR328
0511	24	PK		6-7	24-33-11	D00652		42		D40550P	46			YC051-YC052
0511	24	PK		8-10	24-33-11	D00652		42		D40550P	46			YC053-YC055
0511	24	PK		8-11	24-33-11	D00652		42		D40550P	46			YC056-YC058
0511	24	PK		9-0	24-33-11	D00652		42		D40550P	46			YC059-YC064
0511	24	PK		6-11	24-33-11	D00652		42		D40550P	46			YC065-YD158, YL951-YR328
0512	24	PK		6-7	24-33-11	D00652		10		D40550P	36			YC051-YC052
0512	24	PK		8-10	24-33-11	D00652		10		D40550P	36			YC053-YC055
0512	24	PK		8-11	24-33-11	D00652		10		D40550P	36			YC056-YC058
0512	24	PK		9-0	24-33-11	D00652		10		D40550P	36			YC059-YC064
0512	24	PK		6-11	24-33-11	D00652		10		D40550P	36			YC065-YD158, YL951-YR328
0513	24	PK		6-7	24-33-11	D00652		11		D40550P	54			YC051-YC052
0513	24	PK		8-10	24-33-11	D00652		11		D40550P	54			YC053-YC055
0513	24	PK		8-11	24-33-11	D00652		11		D40550P	54			YC056-YC058
0513	24	PK		9-0	24-33-11	D00652		11		D40550P	54			YC059-YC064

WIRE LIST

D280A108

91-21-11

Section W2500

Page 2

Nov 12/2012

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2508	286A2508			P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)											
0513	24		PK		6-11	24-33-11	D00652	11			D40550P	54			YC065-YD158, YL951-YR328
0514	24		B6		6-7	24-33-11	D00652	23			D40550P	42			YC051-YC052
0514	24		B6		8-10	24-33-11	D00652	23			D40550P	42			YC053-YC055
0514	24		B6		8-11	24-33-11	D00652	23			D40550P	42			YC056-YC058
0514	24		B6		9-0	24-33-11	D00652	23			D40550P	42			YC059-YC064
0514	24		B6		6-11	24-33-11	D00652	23			D40550P	42			YC065-YD158, YL951-YR328
0515	24		B6		7-1	24-34-11	D01086	5			D40550P	47			YC051-YC052
0515	24		B6		9-3	24-34-11	D01086	5			D40550P	47			YC053-YC064
0515	24		B6		7-3	24-34-11	D01086	5			D40550P	47			YC065-YD158, YL951-YR328
0516	24		B6		7-1	24-34-11	D01086	25			D40550P	48			YC051-YC052
0516	24		B6		9-3	24-34-11	D01086	25			D40550P	48			YC053-YC064
0516	24		B6		7-3	24-34-11	D01086	25			D40550P	48			YC065-YD158, YL951-YR328
0517	20		CQ		2-11	24-34-11	D01086	26			GD00503	DC..	1A		YC051-YC058
0517	20		CQ		2-8	24-34-11	D01086	26			GD00503	DC..	1A		YC059-YC064
0517	20		CQ		2-9	24-34-11	D01086	26			GD00503	DC..	1A		YC065-YD158, YL951-YR328
0519	24		B6		1-10	24-34-11	D01086	35			D10596	47			YC051-YC052
0519	24		B6		1-9	24-34-11	D01086	35			D10596	47			YC053-YC058
0519	24		B6		2-0	24-34-11	D01086	35			D10596	47			YC059-YC064
0519	24		B6		2-1	24-34-11	D01086	35			D10596	47			YC065-YD158, YL951-YR328
0520	24		B6		6-7	24-34-11	D10596	30			D40550P	49			YC051-YC052
0520	24		B6		8-9	24-34-11	D10596	30			D40550P	49			YC053-YC058
0520	24		B6		9-0	24-34-11	D10596	30			D40550P	49			YC059-YC064
0520	24		B6		6-11	24-34-11	D10596	30			D40550P	49			YC065-YD158, YL951-YR328
0521	24		B6		6-7	24-34-11	D00652	22			D40550P	30			YC051-YC052
0521	24		B6		8-10	24-34-11	D00652	22			D40550P	30			YC053-YC055
0521	24		B6		8-11	24-34-11	D00652	22			D40550P	30			YC056-YC058
0521	24		B6		9-0	24-34-11	D00652	22			D40550P	30			YC059-YC064
0521	24		B6		6-11	24-34-11	D00652	22			D40550P	30			YC065-YD158, YL951-YR328
0523	18		CQ		7-1	24-11-11	D01086	23	18		D40550P	13	18		YC051-YC052
0523	18		CQ		9-3	24-11-11	D01086	23	18		D40550P	13	18		YC053-YC064

WIRE LIST

D280A108

91-21-11

Section W2500

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2508	286A2508				P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)										
0523	18		CQ		7-3	24-11-11	D01086		23	18	D40550P	13	18		YC065-YD158, YL951-YR328
0524	18		CQ		30-2	24-11-11	D01086		41	18	D40556J	9	18		YC051-YC064
0524	18		CQ		30-3	24-11-11	D01086		41	18	D40556J	9	18		YC065-YD158, YL951-YR328
0528	24		B6		27-8	24-31-11	D10596		52		TB5801X	A002	1A		YC051-YC055
0528	24		B6		27-3	24-31-11	D10596		52		TB5801X	A002	1A		YC056-YC058
0528	24		B6		27-6	24-31-11	D10596		52		TB5801X	A002	1A		YC059-YD158, YL951-YR328
0529	24		B6		21-4	24-33-11	D00652		9		D48106P	A09			YC051-YC055
0529	24		B6		21-5	24-33-11	D00652		9		D48106P	A09			YC056-YC058
0529	24		B6		21-6	24-33-11	D00652		9		D48106P	A09			YC059-YD158, YL951-YR328
0531	24		B6		27-8	24-31-12	D00652		8		TB5801X	A003	1A		YC051-YC052
0531	24		B6		27-9	24-31-12	D00652		8		TB5801X	A003	1A		YC053-YC055
0531	24		B6		27-5	24-31-12	D00652		8		TB5801X	A003	1A		YC056-YC058
0531	24		B6		27-6	24-31-12	D00652		8		TB5801X	A003	1A		YC059-YD158, YL951-YR328
0532	24		B6		30-5	29-33-11	D00642		5		D40556J	2			YC051-YC052
0532	24		B6		30-3	29-33-11	D00642		5		D40556J	2			YC053-YC058
0532	24		B6		30-4	29-33-11	D00642		5		D40556J	2			YC059-YD158, YL951-YR328
0533	24		B6		26-1	24-31-11	D40550P		40		TB5801X	A001	1A		YC051-YC052, YC065-YD158, YL951-YR328
0533	24		B6		25-11	24-31-11	D40550P		40		TB5801X	A001	1A		YC053-YC055
0533	24		B6		25-6	24-31-11	D40550P		40		TB5801X	A001	1A		YC056-YC064
0534	24		B6		26-1	24-31-12	D40550P		45		TB5801X	B001	1A		YC051-YC052, YC065-YD158, YL951-YR328
0534	24		B6		25-11	24-31-12	D40550P		45		TB5801X	B001	1A		YC053-YC055
0534	24		B6		25-6	24-31-12	D40550P		45		TB5801X	B001	1A		YC056-YC064
0535	24		B6		26-1	24-31-12	D40550P		51		TB5801X	B002	1A		YC051-YC052, YC065-YD158, YL951-YR328
0535	24		B6		25-11	24-31-12	D40550P		51		TB5801X	B002	1A		YC053-YC055
0535	24		B6		25-6	24-31-12	D40550P		51		TB5801X	B002	1A		YC056-YC064
0536	22		PA		21-3	24-28-11	D10596		40		D48106P	A03			YC051-YC058

WIRE LIST

D280A108

91-21-11

Section W2500

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2508	286A2508			P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)											
0536	22		PA		21-6	24-28-11	D10596	40			D48106P	A03			YC059-YD158, YL951-YR328
0537	22		PA		21-3	24-28-11	D10596	53			D48106P	A04			YC051-YC058
0537	22		PA		21-6	24-28-11	D10596	53			D48106P	A04			YC059-YD158, YL951-YR328
1001	20		VF	AA	1-10	33-14-12	D00918	= A1			S00238	2	C		YC051-YC064
1001	20		VF	AA	1-4	33-14-12	D00918	= A1			S00238	2	C		YC065-YD158, YL951-YR328
1001Z				AA	0-0	33-14-12	S00238			FA	D00918	= C1			YC051-YD158, YL951-YR328
1005	20		CQ		3-5	33-18-37	L01492	3	B		L00001	3	B	*	YL951-YR328
1006	20		CQ		3-5	33-18-37	L01492	4	B		L00001	4	B	*	YL951-YR328
1007	20		CQ		3-5	33-18-37	L01492	2	B		L00001	2	B	*	YL951-YR328
1008	22		PA		10-3	23-42-11	L01492	1	B		SP00593		9		YL951-YR328
1010	22		PA		10-4	23-42-11	S01148		C	Z2	SP00593		9		YL951-YR328
1011	22		PA		16-3	23-42-11	S01148		NO	Z2	SP00613		9		YL951-YR328
1012	22		PA		16-3	23-42-11	S01148		NC	Z2	SP00617		9		YL951-YR328
1303R	20		X5	EQ	30-0	26-12-11	D00680	33			D40556J	29			YC051-YC058
1303R	20		X5	EQ	30-1	26-12-11	D00680	33			D40556J	29			YC059-YD158, YL951-YR328
1303Z				EQ	0-0	26-12-11	D00680		DED		D40556J	DED			YC051-YD158, YL951-YR328
1304R	20		X5	ER	30-0	26-12-11	D00680	34			D40556J	30			YC051-YC058
1304R	20		X5	ER	30-1	26-12-11	D00680	34			D40556J	30			YC059-YD158, YL951-YR328
1304Z				ER	0-0	26-12-11	D00680		DED		D40556J	DED			YC051-YD158, YL951-YR328
1305R	20		X5	ES	30-0	26-12-11	D00680	23			D40556J	47			YC051-YC058
1305R	20		X5	ES	30-1	26-12-11	D00680	23			D40556J	47			YC059-YD158, YL951-YR328
1305Z				ES	0-0	26-12-11	D00680		DED		D40556J	DED			YC051-YD158, YL951-YR328
1306R	20		X5	ET	30-0	26-12-11	D00680	21			D40556J	48			YC051-YC058
1306R	20		X5	ET	30-1	26-12-11	D00680	21			D40556J	48			YC059-YD158, YL951-YR328
1306Z				ET	0-0	26-12-11	D00680		DED		D40556J	DED			YC051-YD158, YL951-YR328
1307R	20		X5	EU	30-2	26-12-11	D00646	8			D40556J	49			YC051-YC052
1307R	20		X5	EU	29-10	26-12-11	D00646	8			D40556J	49			YC053-YC058

WIRE LIST

D280A108

91-21-11

Section W2500

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2508	286A2508			P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)											
1307R	20	X5		EU	29-11	26-12-11	D00646		8		D40556J	49			YC059-YD158, YL951-YR328
1307Z				EU	0-0	26-12-11	D00646		DED		D40556J	DED			YC051-YD158, YL951-YR328
2001B	22	X2		GA	38-10	21-31-11	D10724		24		D40554P	B08			YC051-YC052
2001B	22	X2		GA	38-8	21-31-11	D10724		24		D40554P	B08			YC053-YC055
2001B	22	X2		GA	38-6	21-31-11	D10724		24		D40554P	B08			YC056-YC058
2001B	22	X2		GA	38-9	21-31-11	D10724		24		D40554P	B08			YC059-YD158, YL951-YR328
2001R	22	X2		GA	0-0	21-31-11	D10724		25		D40554P	A08			YC051-YD158, YL951-YR328
2001Z				GA	0-0	21-31-11	D10724			AB	D40554P	PERG	1F		YC051-YD158, YL951-YR328
2002B	20	X2		GB	7-1	33-14-12	S00238			FA	GD00264	DC..	1A		YC051-YC052
2002B	20	X2		GB	9-6	33-14-12	S00238			FA	GD00264	DC..	1A		YC053-YC064
2002B	20	X2		GB	7-5	33-14-12	S00238			FA	GD00264	DC..	1A		YC065-YD158, YL951-YR328
2002R	20	X2		GB	0-0	33-14-12	S00238		1	C	SM00001		W		YC051-YD158, YL951-YR328
2002Z				GB	0-0	33-14-12	S00238			DED	GD00264	DED			YC051-YD158, YL951-YR328
2003B	24	Y2		AB	26-5	34-61-15	D40556J		5		TB0261X	B014	1A		YC051-YC052
2003B	24	Y2		AB	27-2	34-61-15	D40556J		5		TB0261X	B014	1A		YC053-YC064
2003B	24	Y2		AB	27-11	34-61-15	D40556J		5		TB0261X	B014	1A		YC065-YD158
2003R	24	Y2		AB	0-0	34-61-15	D40556J		4		TB0261X	A014	1A		YC051-YD158
2003Z				AB	0-0	34-61-15	D40556J		14		GB00261	ST..	1A		YC051-YD158
2201B	24	Y2		KA	21-4	24-31-11	D00652		32		D48106P	A06			YC051-YC055
2201B	24	Y2		KA	21-5	24-31-11	D00652		32		D48106P	A06			YC056-YC058
2201B	24	Y2		KA	21-6	24-31-11	D00652		32		D48106P	A06			YC059-YD158, YN231
2201B	20	X2		KA	21-6	24-31-11	D00652		32		D48106P	A06			YL951-YL999, YN232-YR328
2201R	24	Y2		KA	0-0	24-31-11	D00652		50		D48106P	A05			YC051-YD158, YN231
2201R	20	X2		KA	0-0	24-31-11	D00652		50		D48106P	A05			YL951-YL999, YN232-YR328
2201Z				KA	0-0	24-31-11	D00652			DED	D48106P	DED			YC051-YD158, YL951-YR328
2202B	24	Y2		KB	21-4	24-31-12	D00652		36		D48106P	A08			YC051-YC055
2202B	24	Y2		KB	21-5	24-31-12	D00652		36		D48106P	A08			YC056-YC058
2202B	24	Y2		KB	21-6	24-31-12	D00652		36		D48106P	A08			YC059-YD158, YN231

WIRE LIST

D280A108

91-21-11

Section W2500

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W2508	286A2508			P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)										
2202B	20	X2	KB	21-6	24-31-12	D00652	36			D48106P	A08			YL951-YL999, YN232-YR328
2202R	24	Y2	KB	0-0	24-31-12	D00652	54			D48106P	A07			YC051-YD158, YN231
2202R	20	X2	KB	0-0	24-31-12	D00652	54			D48106P	A07			YL951-YL999, YN232-YR328
2202Z			KB	0-0	24-31-12	D00652	DED			D48106P	DED			YC051-YD158, YL951-YR328
2601B	22	X2	SA	21-8	30-21-11	D00462	12			D48106P	B04			YC051-YC052, YC065-YD158, YL951-YR328
2601B	22	X2	SA	21-6	30-21-11	D00462	12			D48106P	B04			YC053-YC058
2601B	22	X2	SA	21-7	30-21-11	D00462	12			D48106P	B04			YC059-YC064
2601R	22	X2	SA	0-0	30-21-11	D00462	15			D48106P	B03			YC051-YD158, YL951-YR328
2601Z			SA	0-0	30-21-11	D00462	DED			D48106P	DED			YC051-YD158, YL951-YR328
2602B	24	Y2	SB	30-10	76-21-11	D00626	12			D40556J	22			YC051-YC052
2602B	24	Y2	SB	30-11	76-21-11	D00626	12			D40556J	22			YC053-YC058
2602B	24	Y2	SB	30-9	76-21-11	D00626	12			D40556J	22			YC059-YD158, YL951-YR328
2602R	24	Y2	SB	0-0	76-21-11	D00626	11			D40556J	21			YC051-YD158, YL951-YR328
2602Z			SB	0-0	76-21-11	D00626	DED			D40556J	DED			YC051-YD158, YL951-YR328
3001B	24	Y3	WA	38-10	21-31-11	D10724	30			D40554P	B05			YC051-YC052
3001B	24	Y3	WA	38-8	21-31-11	D10724	30			D40554P	B05			YC053-YC055
3001B	24	Y3	WA	38-6	21-31-11	D10724	30			D40554P	B05			YC056-YC058
3001B	24	Y3	WA	38-9	21-31-11	D10724	30			D40554P	B05			YC059-YD158, YL951-YR328
3001R	24	Y3	WA	0-0	21-31-11	D10724	18			D40554P	A05			YC051-YD158, YL951-YR328
3001Y	24	Y3	WA	0-0	21-31-11	D10724	31			D40554P	A06			YC051-YD158, YL951-YR328
3001Z			WA	0-0	21-31-11	D10724			AB	D40554P	PERG	1F		YC051-YD158, YL951-YR328
5501	20	CQ		7-7	21-31-11	D10724	15			D40550P	1			YC051-YC052
5501	20	CQ		9-8	21-31-11	D10724	15			D40550P	1			YC053-YC058
5501	20	CQ		9-11	21-31-11	D10724	15			D40550P	1			YC059-YC064

WIRE LIST

D280A108

91-21-11

Section W2500

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2508	286A2508				P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)										
5501	20		CQ		7-10	21-31-11	D10724		15		D40550P		1		YC065-YD158, YL951-YR328
5502	20		CQ		3-2	21-31-11	D10724		28		GD00504	DC..	1A		YC051-YC052
5502	20		CQ		2-11	21-31-11	D10724		28		GD00518	DC..	1A		YC053-YC058
5502	20		CQ		3-2	21-31-11	D10724		28		GD00518	DC..	1A		YC059-YD158, YL951-YR328
5504	24		B6		5-1	21-31-11	D10724		1		TB0505Y	B013	1A		YC051-YC052
5504	24		B6		5-0	21-31-11	D10724		1		TB0505Y	B013	1A		YC053-YC058
5504	24		B6		6-0	21-31-11	D10724		1		TB0505Y	B013	1A		YC059-YC064
5504	24		B6		6-4	21-31-11	D10724		1		TB0505Y	B013	1A		YC065-YD158, YL951-YR328
5505	24		B6		4-4	21-31-11	TB0505Y	A013	1A		D40550P		44		YC051-YC052
5505	24		B6		6-11	21-31-11	TB0505Y	A013	1A		D40550P		44		YC053-YC058
5505	24		B6		6-10	21-31-11	TB0505Y	A013	1A		D40550P		44		YC059-YC064
5505	24		B6		4-6	21-31-11	TB0505Y	A013	1A		D40550P		44		YC065-YD158, YL951-YR328
5506	22		CQ		7-11	21-33-11	D00654		8		D40550P		6		YC051-YC052, YC065-YD158, YL951, YN231
5506	22		CQ		9-11	21-33-11	D00654		8		D40550P		6		YC053-YC058
5506	22		CQ		10-0	21-33-11	D00654		8		D40550P		6		YC059
5506	22		CQ		8-4	21-33-11	TB0502Y	B009	1A		D40550P		6		YC060-YC064
5506	22		CQ		4-7	21-33-11	TB0502Y	B009	1A		D40550P		6		YL952-YL999, YN232-YR328
5507	22		PA		29-6	21-33-11	D00654		6		D46108P		3		YC051-YC052, YC059, YC065-YD158, YL951, YN231
5507	22		PA		29-5	21-33-11	D00654		6		D46108P		3		YC053-YC058
5507	22		CQ		41-8	21-33-11	D00654		6		D46108P		3		YC060-YC064
5507	22		CQ		29-6	21-33-11	D00654		6		D46108P		3		YL952-YL999, YN232-YR328
5508	22		PA		29-6	21-33-11	D00654		7		D46108P		4		YC051-YC052, YC059, YC065-YD158, YL951, YN231
5508	22		PA		29-5	21-33-11	D00654		7		D46108P		4		YC053-YC058
5508	22		CQ		41-8	21-33-11	SP00575		W		D46108P		4		YC060-YC064

WIRE LIST
D280A108

91-21-11
Section W2500
Page 8
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W2508	286A2508				P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)												
5508	22		CQ		29-6		21-33-11	D00654		7		D46108P		4		YL952-YL999, YN232-YR328	
5509	24		B6		4-8		21-51-11	D00646		17		TB0504Y	A001	1A		YC051-YC052	
5509	24		B6		4-3		21-51-11	D00646		17		TB0504Y	A001	1A		YC053-YC058	
5509	24		B6		4-6		21-51-11	D00646		17		TB0504Y	A001	1A		YC059-YC064	
5509	24		B6		4-10		21-51-11	D00646		17		TB0504Y	A001	1A		YC065-YD158, YL951-YL999, YR301-YR328	
5509	24		B6		6-11		21-51-11	D00646		17		D40550P		26		YN231-YN501	
5510	24		B6		38-3		21-51-11	D00646		42		D40554P	A03			YC051-YC052	
5510	24		B6		38-0		21-51-11	D00646		42		D40554P	A03			YC053-YC055	
5510	24		B6		37-9		21-51-11	D00646		42		D40554P	A03			YC056-YC058	
5510	24		B6		37-10		21-51-11	D00646		42		D40554P	A03			YC059-YD158, YL951-YR328	
5511	24		B6		38-3		21-51-11	D00646		13		D40554P	B03			YC051-YC052	
5511	24		B6		38-0		21-51-11	D00646		13		D40554P	B03			YC053-YC055	
5511	24		B6		37-9		21-51-11	D00646		13		D40554P	B03			YC056-YC058	
5511	24		B6		37-10		21-51-11	D00646		13		D40554P	B03			YC059-YD158, YL951-YR328	
5512	22		PA		28-8		21-25-11	D00646		53		D46108P		2		YC051-YC052	
5512	22		PA		28-5		21-25-11	D00646		53		D46108P		2		YC053-YC058	
5512	22		PA		28-6		21-25-11	D00646		53		D46108P		2		YC059-YD158, YL951-YL999, YR301-YR328	
5513	24		B6		38-3		21-51-11	D00646		41		D40554P	B09			YC051-YC052	
5513	24		B6		38-0		21-51-11	D00646		41		D40554P	B09			YC053-YC055	
5513	24		B6		37-9		21-51-11	D00646		41		D40554P	B09			YC056-YC058	
5513	24		B6		37-10		21-51-11	D00646		41		D40554P	B09			YC059-YD158, YL951-YR328	
5514	24		B6		38-3		21-51-11	D00646		45		D40554P	A10			YC051-YC052	
5514	24		B6		38-0		21-51-11	D00646		45		D40554P	A10			YC053-YC055	
5514	24		B6		37-9		21-51-11	D00646		45		D40554P	A10			YC056-YC058	
5514	24		B6		37-10		21-51-11	D00646		45		D40554P	A10			YC059-YD158, YL951-YR328	
5515	24		B6		38-3		21-51-11	D00646		23		D40554P	B10			YC051-YC052	
5515	24		B6		38-0		21-51-11	D00646		23		D40554P	B10			YC053-YC055	
5515	24		B6		37-9		21-51-11	D00646		23		D40554P	B10			YC056-YC058	
5515	24		B6		37-10		21-51-11	D00646		23		D40554P	B10			YC059-YD158, YL951-YR328	

WIRE LIST

D280A108

91-21-11

Section W2500

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W2508	286A2508				P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)											
5516	24	B6		38-3	21-51-11	D00646		24			D40554P	A11		YC051-YC052		
5516	24	B6		38-0	21-51-11	D00646		24			D40554P	A11		YC053-YC055		
5516	24	B6		37-9	21-51-11	D00646		24			D40554P	A09		YC056-YC058		
5516	24	B6		37-10	21-51-11	D00646		24			D40554P	A09		YC059-YD158, YL951-YR328		
5517	24	PK		38-3	21-51-11	D00646		35			D40554P	A13		YC051-YC052		
5517	24	PK		38-0	21-51-11	D00646		35			D40554P	A13		YC053-YC055		
5517	24	PK		37-9	21-51-11	D00646		35			D40554P	A04		YC056-YC058		
5517	24	PK		37-10	21-51-11	D00646		35			D40554P	A04		YC059-YD158, YL951-YR328		
5518	24	B6		28-8	21-51-11	D00646		46			D46108P	8		YC051-YC052		
5518	24	B6		28-5	21-51-11	D00646		46			D46108P	8		YC053-YC058		
5518	24	B6		28-6	21-51-11	D00646		46			D46108P	8		YC059-YD158, YL951-YR328		
5519	24	B6		38-3	21-51-15	D00646		29			D40554P	B11		YC051-YC052		
5519	24	B6		38-0	21-51-15	D00646		29			D40554P	B11		YC053-YC055		
5519	24	B6		37-9	21-51-15	D00646		29			D40554P	B07		YC056-YC058		
5519	24	B6		37-10	21-51-15	D00646		29			D40554P	B07		YC059-YD158, YL951-YR328		
5520	24	PK		38-3	21-51-15	D00646		37			D40554P	A12		YC051-YC052		
5520	24	PK		38-0	21-51-15	D00646		37			D40554P	A12		YC053-YC055		
5520	24	PK		37-9	21-51-15	D00646		37			D40554P	A07		YC056-YC058		
5520	24	PK		37-10	21-51-15	D00646		37			D40554P	A07		YC059-YD158, YL951-YL999, YR301-YR328		
5520	24	PK		38-0	21-51-15	D00680		10			D40554P	A07		YN231-YN501		
5521	20	CQ		6-5	33-14-12	S00103		2	C		D40550P	21		YC051-YC052, YC065-YD158, YL951-YR328		
5521	20	CQ		8-7	33-14-12	S00103		2	C		D40550P	21		YC053-YC058		
5521	20	CQ		8-6	33-14-12	S00103		2	C		D40550P	21		YC059-YC064		
5522	20	CQ		6-5	33-14-12	S00103		1	C	*	D40550P	52		YC051-YC052, YC065-YD158, YL951-YR328		
5522	20	CQ		8-7	33-14-12	S00103		1	C	*	D40550P	52		YC053-YC058		
5522	20	CQ		8-6	33-14-12	S00103		1	C	*	D40550P	52		YC059-YC064		
5523	20	CQ		9-4	33-14-12	S00103		1	C	*	L00273	= P	C	YC051-YC058		
5523	20	CQ		9-3	33-14-12	S00103		1	C	*	L00273	= P	C	YC059-YD158, YL951-YR328		

WIRE LIST

D280A108

91-21-11

Section W2500

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2508		286A2508			P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)											
5524		20		CQ		4-7	33-18-31	TB0506Z	A001	1A		D40550P	24			YC051-YC052
5524		20		CQ		7-1	33-18-31	TB0506Z	A001	1A		D40550P	24			YC053-YC058
5524		20		CQ		7-0	33-18-31	TB0506Z	A001	1A		D40550P	24			YC059-YC064
5524		20		CQ		4-6	33-18-31	TB0506Z	A001	1A		D40550P	24			YC065-YD158, YL951-YR328
5525		20		CQ		4-7	33-18-31	D00630		18		TB0506Z	A001	1A		YC051-YC052
5525		20		CQ		6-10	33-18-31	D00630		18		TB0508Y	B009	1A		YC053-YC058
5525		20		CQ		5-5	33-18-31	D00630		18		TB0508Y	B009	1A		YC059-YD158, YL951-YR328
5526		20		CQ		4-8	33-18-31	TB0502Z	A001	1A		D40550P	16			YC051-YC052, YC065-YD158, YL951-YR328
5526		20		CQ		7-1	33-18-31	TB0502Z	A001	1A		D40550P	16			YC053-YC058
5526		20		CQ		7-0	33-18-31	TB0502Z	A001	1A		D40550P	16			YC059-YC064
5527		20		CQ		4-8	33-18-31	D00630		7		TB0502Z	A001	1A		YC051-YC052
5527		20		CQ		3-1	33-18-31	D00630		7		TB0507Z	A001	1A		YC053-YC058
5527		20		CQ		2-6	33-18-31	D00630		7		TB0507Z	A001	1A		YC059-YD158, YL951-YR328
5528		20		CQ		2-9	33-18-31	D00630		16		GD00503	DC..	1A		YC051-YC052
5528		20		CQ		2-11	33-18-31	D00630		16		GD00503	DC..	1A		YC053-YC058
5528		20		CQ		2-5	33-18-31	D00630		16		GD00503	DC..	1A		YC059-YD158, YL951-YR328
5529		20		CQ		4-8	33-18-32	TB0502Z	B013	1A		D40550P	9			YC051-YC052
5529		20		CQ		8-10	33-18-32	TB0507Y	A011	1A		D40550P	9			YC053-YC058
5529		20		CQ		8-3	33-18-32	TB0507Y	A011	1A		D40550P	9			YC059-YC064
5529		20		CQ		6-2	33-18-32	TB0507Y	A011	1A		D40550P	9			YC065-YD158, YL951-YR328
5530		22		PA		38-3	21-25-11	D40554P		B12		D00646	54			YC051-YC052
5530		22		PA		38-0	21-25-11	D40554P		B12		D00646	54			YC053-YC055
5530		22		PA		37-9	21-25-11	D40554P		B06		D00646	54			YC056-YC058
5530		22		PA		37-10	21-25-11	D40554P		B06		D00646	54			YC059-YD158, YL951-YL999, YR301-YR328
5531		20		CQ		4-4	33-18-32	TB0501Y	A013	1A		D40550P	31			YC051-YC052
5531		20		CQ		6-11	33-18-32	TB0501Y	A013	1A		D40550P	31			YC053-YC058
5531		20		CQ		6-10	33-18-32	TB0501Y	A013	1A		D40550P	31			YC059-YC064
5531		20		CQ		4-6	33-18-32	TB0501Y	A013	1A		D40550P	31			YC065-YD158, YL951-YR328
5532		20		CQ		5-2	33-18-32	D00626		5		TB0501Y	A013	1A		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W2500

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2508	286A2508				P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)											
5532	20		CQ		5-4	33-18-32		D00626		5		TB0501Y	A013	1A		YC053-YC058
5532	20		CQ		5-5	33-18-32		D00626		5		TB0501Y	A013	1A		YC059-YC064
5532	20		CQ		6-3	33-18-32		D00626		5		TB0501Y	A013	1A		YC065-YD158, YL951-YR328
5533	20		CQ		4-3	33-18-32		TB0503Z	A001	1A		D40550P		33		YC051-YC052
5533	20		CQ		6-10	33-18-32		TB0503Z	A001	1A		D40550P		33		YC053-YC058
5533	20		CQ		6-9	33-18-32		TB0503Z	A001	1A		D40550P		33		YC059-YC064
5533	20		CQ		4-2	33-18-32		TB0503Z	A001	1A		D40550P		33		YC065-YD158, YL951-YR328
5534	20		CQ		5-1	33-18-32		D00626		14		TB0503Z	A001	1A		YC051-YC052
5534	20		CQ		3-10	33-18-32		D00626		14		TB0507Y	A005	1A		YC053-YC058
5534	20		CQ		3-3	33-18-32		D00626		14		TB0507Y	A005	1A		YC059-YD158, YL951-YR328
5535	20		CQ		4-4	33-18-33		TB0503Z	A009	1A		D40550P		15		YC051-YC052
5535	20		CQ		7-1	33-18-33		TB0506Z	B001	1A		D40550P		15		YC053-YC058
5535	20		CQ		7-0	33-18-33		TB0506Z	B001	1A		D40550P		15		YC059-YC064
5535	20		CQ		4-6	33-18-33		TB0506Z	B001	1A		D40550P		15		YC065-YD158, YL951-YR328
5536	20		CQ		4-5	33-18-33		D00636		27		TB0503Z	A009	1A		YC051-YC052
5536	20		CQ		2-11	33-18-33		D00636		27		TB0507Y	A007	1A		YC053-YC058
5536	20		CQ		2-8	33-18-33		D00636		27		TB0507Y	A007	1A		YC059-YC064
5536	20		CQ		2-9	33-18-33		D00636		27		TB0507Y	A007	1A		YC065-YD158, YL951-YR328
5537	20		CQ		5-5	33-18-33		D00730		20		TB0503Z	A009	1A		YC051-YC052
5537	20		CQ		4-1	33-18-33		D00730		20		TB0507Y	A007	1A		YC053-YC058
5537	20		CQ		3-7	33-18-33		D00730		20		TB0507Y	A007	1A		YC059-YD158, YL951-YR328
5538	20		CQ		3-11	33-18-33		D00634		2		GD00503	DC..	1A		YC051-YC058
5538	20		CQ		3-7	33-18-33		D00634		2		GD00503	DC..	1A		YC059-YD158, YL951-YR328
5539	20		CQ		3-11	33-18-33		D00634		10		GD00503	DC..	1A		YC051-YC058
5539	20		CQ		3-7	33-18-33		D00634		10		GD00503	DC..	1A		YC059-YD158, YL951-YR328
5540	20		CQ		6-4	33-18-33		D00634		23		TB0502Z	A001	1A		YC051-YC052
5540	20		CQ		4-2	33-18-33		D00634		23		TB0507Z	A001	1A		YC053-YC058
5540	20		CQ		3-8	33-18-33		D00634		23		TB0507Z	A001	1A		YC059-YD158, YL951-YR328
5541	20		CQ		4-4	33-18-33		D10596		45		TB0502Z	A001	1A		YC051-YC052
5541	20		CQ		2-7	33-18-33		D10596		45		TB0507Z	A001	1A		YC053-YC058

WIRE LIST

D280A108

91-21-11

Section W2500

Page 12

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W2508	286A2508				P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)										
5541	20		CQ		2-6	33-18-33	D10596		45		TB0507Z	A001	1A		YC059-YD158, YL951-YR328
5542	20		CQ		4-4	33-18-33	D10596		51		TB0502Z	A013	1A		YC051-YC052
5542	20		CQ		2-6	33-18-33	D10596		51		TB0507Y	B007	1A		YC053-YC058
5542	20		CQ		2-5	33-18-33	D10596		51		TB0507Y	B007	1A		YC059-YD158, YL951-YR328
5543	20		CQ		2-5	33-18-33	D10596		48		GD00503	DC..	1A		YC051-YD158, YL951-YR328
5544	20		CQ		4-5	33-18-33	D01086		19		TB0503Z	A001	1A		YC051-YC052
5544	20		CQ		3-1	33-18-33	D01086		19		TB0507Y	A005	1A		YC053-YC058
5544	20		CQ		2-8	33-18-33	D01086		19		TB0507Y	A005	1A		YC059-YC064
5544	20		CQ		2-9	33-18-33	D01086		19		TB0507Y	A005	1A		YC065-YD158, YL951-YR328
5545	20		CQ		4-10	33-18-33	D01086		18		TB0502Z	A013	1A		YC051-YC052
5545	20		CQ		3-1	33-18-33	D01086		18		TB0507Y	B007	1A		YC053-YC058
5545	20		CQ		2-8	33-18-33	D01086		18		TB0507Y	B007	1A		YC059-YC064
5545	20		CQ		2-9	33-18-33	D01086		18		TB0507Y	B007	1A		YC065-YD158, YL951-YR328
5546	20		CQ		6-2	33-18-33	D00722		19		TB0502Z	A013	1A		YC051-YC052
5546	20		CQ		3-11	33-18-33	D00722		19		TB0507Y	B007	1A		YC053-YC058
5546	20		CQ		3-7	33-18-33	D00722		19		TB0507Y	B007	1A		YC059-YD158, YL951-YR328
5547	20		CQ		4-8	33-18-33	TB0502Z	A013	1A		D40550P		17		YC051-YC052
5547	20		CQ		7-0	33-18-33	TB0502Y	A009	1A		D40550P		17		YC053-YC058
5547	20		CQ		6-11	33-18-33	TB0502Y	A009	1A		D40550P		17		YC059-YC064
5547	20		CQ		4-7	33-18-33	TB0502Y	A009	1A		D40550P		17		YC065-YD158, YL951-YR328
5548	20		CQ		4-8	33-18-34	TB0502Y	B011	1A		D40550P		8		YC051-YC052
5548	20		CQ		7-0	33-18-34	TB0502Y	B011	1A		D40550P		8		YC053-YC058
5548	20		CQ		6-11	33-18-34	TB0502Y	B011	1A		D40550P		8		YC059-YC064
5548	20		CQ		4-7	33-18-34	TB0502Y	B011	1A		D40550P		8		YC065-YD158, YL951-YR328
5549	20		CQ		4-4	33-18-34	D00644		32		TB0502Y	B011	1A		YC051-YC052
5549	20		CQ		2-4	33-18-34	D00644		32		TB0508Y	B005	1A		YC053-YC058
5549	20		CQ		2-0	33-18-34	D00644		32		TB0508Y	B005	1A		YC059-YD158, YL951-YR328
5550	20		CQ		4-2	33-18-34	D00638		32		TB0506Z	A001	1A		YC051-YC052
5550	20		CQ		2-3	33-18-34	D00638		32		TB0508Y	B009	1A		YC053-YC058

WIRE LIST

D280A108

91-21-11

Section W2500

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2508	286A2508			P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)											
5550	20		CQ		1-11	33-18-34	D00638		32		TB0508Y	B009	1A		YC059-YD158, YL951-YR328
5551	20		CQ		4-9	33-18-34	D00648		24		TB0506Z	A001	1A		YC051-YC052
5551	20		CQ		2-10	33-18-34	D00648		24		TB0508Y	B009	1A		YC053-YC058
5551	20		CQ		2-6	33-18-34	D00648		24		TB0508Y	B009	1A		YC059-YC064
5551	20		CQ		2-4	33-18-34	D00648		24		TB0508Y	B009	1A		YC065-YD158, YL951-YR328
5552	20		CQ		3-10	33-18-34	D00638		11		TB0503Z	A001	1A		YC051-YC052
5552	20		CQ		2-3	33-18-34	D00638		11		TB0508Y	A005	1A		YC053-YC058
5552	20		CQ		1-10	33-18-34	D00638		11		TB0508Y	A005	1A		YC059-YD158, YL951-YR328
5553	20		CQ		4-9	33-18-34	D00462		3		TB0502Z	A001	1A		YC051-YC052
5553	20		CQ		2-9	33-18-34	D00462		3		TB0508Z	A001	1A		YC053-YC058
5553	20		CQ		2-5	33-18-34	D00462		3		TB0508Z	A001	1A		YC059-YC064
5553	20		CQ		2-6	33-18-34	D00462		3		TB0508Z	A001	1A		YC065-YD158, YL951-YR328
5554	20		CQ		0-7	33-18-35	TB0502Z	B001	1A		TB0502Z	A001	1A		YC051-YC052
5555	20		CQ		4-9	33-18-34	D00462		2		TB0502Z	B013	1A		YC051-YC052
5555	20		CQ		2-9	33-18-34	D00462		2		TB0508Y	A009	1A		YC053-YC058
5555	20		CQ		2-4	33-18-34	D00462		2		TB0508Y	A009	1A		YC059-YC064
5555	20		CQ		2-5	33-18-34	D00462		2		TB0508Y	A009	1A		YC065-YD158, YL951-YR328
5556	20		CQ		4-6	33-18-35	TB0502Y	A023	1A		D40550P	50			YC051-YC052
5556	20		CQ		7-0	33-18-35	TB0502Y	A023	1A		D40550P	50			YC053-YC058
5556	20		CQ		6-10	33-18-35	TB0502Y	A023	1A		D40550P	50			YC059-YC064
5556	20		CQ		4-5	33-18-35	TB0502Y	A023	1A		D40550P	50			YC065-YD158, YL951-YR328
5557	20		CQ		5-3	33-18-35	D00482		5		TB0502Y	A023	1A		YC051-YC052, YC059-YC064
5557	20		CQ		5-0	33-18-35	D00482		5		TB0502Y	A023	1A		YC053-YC055
5557	20		CQ		5-2	33-18-35	D00482		5		TB0502Y	A023	1A		YC056-YC058
5557	20		CQ		6-0	33-18-35	D00482		5		TB0502Y	A023	1A		YC065-YD158, YL951-YR328
5558	20		CQ		4-11	33-18-35	D00482		6		TB0503Z	A001	1A		YC051-YC052
5558	20		CQ		3-5	33-18-35	D00482		6		TB0508Y	A005	1A		YC053-YC055
5558	20		CQ		3-7	33-18-35	D00482		6		TB0508Y	A005	1A		YC056-YC058
5558	20		CQ		2-11	33-18-35	D00482		6		TB0508Y	A005	1A		YC059-YD158, YL951-YR328
5559	20		CQ		5-3	33-18-35	D02486		4		TB0502Z	B001	1A		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W2500

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice				
W2508	286A2508				P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)													
5559	20		CQ		3-4		33-18-35	D02486				4		TB0508Z	A001	1A		YC053-YC058
5559	20		CQ		2-11		33-18-35	D02486				4		TB0508Z	A001	1A		YC059-YD158, YL951-YR328
5560	20		CQ		4-9		33-18-35	D00642				3		TB0501Y	A013	1A		YC051-YC052
5560	20		CQ		4-8		33-18-35	D00642				3		TB0501Y	A013	1A		YC053-YC058
5560	20		CQ		4-11		33-18-35	D00642				3		TB0501Y	A013	1A		YC059-YC064
5560	20		CQ		5-3		33-18-35	D00642				3		TB0501Y	A013	1A		YC065-YD158, YL951-YR328
5561	20		CQ		5-3		33-18-35	D02486				3		TB0502Y	B011	1A		YC051-YC052
5561	20		CQ		3-3		33-18-35	D02486				3		TB0508Y	B005	1A		YC053-YC058
5561	20		CQ		2-10		33-18-35	D02486				3		TB0508Y	B005	1A		YC059-YD158, YL951-YR328
5562	20		CQ		7-1		33-18-36	D00646				9		D40550P		32		YC051-YC052
5562	20		CQ		8-11		33-18-36	D00646				9		D40550P		32		YC053-YC058
5562	20		CQ		9-0		33-18-36	D00646				9		D40550P		32		YC059-YC064
5562	20		CQ		6-11		33-18-36	D00646				9		D40550P		32		YC065-YD158, YL951-YR328
5563	20		CQ		6-11		33-18-36	D00680			20			D40550P		23		YC051-YC052
5563	20		CQ		9-1		33-18-36	D00680			20			D40550P		23		YC053-YC058
5563	20		CQ		9-2		33-18-36	D00680			20			D40550P		23		YC059-YC064
5563	20		CQ		7-1		33-18-36	D00680			20			D40550P		23		YC065-YD158, YL951-YR328
5564	20		CQ		4-3		33-18-36	D00680			22			TB0503Z	B001	1A		YC051-YC052
5564	20		CQ		2-10		33-18-36	D00680			22			TB0508Y	A007	1A		YC053-YC058
5564	20		CQ		2-5		33-18-36	D00680			22			TB0508Y	A007	1A		YC059-YD158, YL951-YR328
5565	20		CQ		4-3		33-18-36	TB0503Z		B001	1A			D40550P		5		YC051-YC052
5565	20		CQ		6-10		33-18-36	TB0503Z		B001	1A			D40550P		5		YC053-YC058
5565	20		CQ		6-9		33-18-36	TB0503Z		B001	1A			D40550P		5		YC059-YC064
5565	20		CQ		4-2		33-18-36	TB0503Z		B001	1A			D40550P		5		YC065-YD158, YL951-YR328
5566	20		CQ		4-10		33-18-36	D00646			5			TB0502Z	B013	1A		YC051-YC052
5566	20		CQ		2-8		33-18-36	D00646			5			TB0508Y	A009	1A		YC053-YC058
5566	20		CQ		2-4		33-18-36	D00646			5			TB0508Y	A009	1A		YC059-YD158, YL951-YR328
5567	20		CQ		4-6		33-18-36	D03996			3			TB0502Z	B013	1A		YC051-YC052
5567	20		CQ		2-8		33-18-36	D03996			3			TB0508Y	A009	1A		YC053-YC058

WIRE LIST

D280A108

91-21-11

Section W2500

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From	To							
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2508	286A2508			P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)											
5567	20		CQ		2-2	33-18-36	D03996		3		TB0508Y	A009	1A		YC059-YD158, YL951-YL999, YR301-YR328
5567	20		CQ		2-5	33-18-36	D00656		11		TB0508Y	A009	1A		YN231-YN501
5568	20		CQ		2-7	33-18-36	D00646		3		GD00504	DC..	1A		YC051-YC052
5568	20		CQ		2-3	33-18-36	D00646		3		GD00518	DC..	1A		YC053-YD158, YL951-YR328
5569	20		CQ		4-10	33-18-36	D00646		6		TB0502Z	B001	1A		YC051-YC052
5569	20		CQ		2-9	33-18-36	D00646		6		TB0508Z	A001	1A		YC053-YC058
5569	20		CQ		2-4	33-18-36	D00646		6		TB0508Z	A001	1A		YC059-YD158, YL951-YR328
5570	20		CQ		4-6	33-18-36	D03998		21		TB0502Z	B001	1A		YC051-YC052
5570	20		CQ		2-7	33-18-36	D03998		21		TB0508Z	A001	1A		YC053-YC058
5570	20		CQ		2-2	33-18-36	D03998		21		TB0508Z	A001	1A		YC059-YD158, YL951-YL999, YR301-YR328
5570	20		CQ		2-5	33-18-36	D00656		12		TB0508Z	A001	1A		YN231-YN501
5571	20		CQ		6-1	33-18-36	D10726		22		TB0502Z	B001	1A		YC051-YC052
5571	20		CQ		3-7	33-18-36	D10726		22		TB0508Z	A001	1A		YC053-YC058
5571	20		CQ		3-4	33-18-36	D10726		22		TB0508Z	A001	1A		YC059-YD158, YL951-YR328
5572	20		CQ		6-0	33-18-37	L00047		1	B	TB0502Y	A009	1A		YC051-YC052
5572	20		CQ		4-1	33-18-37	L00047		1	B	TB0507Y	B005	1A		YC053-YC055
5572	20		CQ		3-11	33-18-37	L00047		1	B	TB0507Y	B005	1A		YC056-YC058
5572	20		CQ		3-6	33-18-37	L00047		1	B	TB0507Y	B005	1A		YC059-YC064
5572	20		CQ		3-7	33-18-37	L00047		1	B	TB0507Y	B005	1A		YC065-YD158, YL951-YR328
5573	20		CQ		1-2	33-18-37	L00047		1	B	L01141		1	B	YC051-YC052
5573	20		CQ		1-3	33-18-37	L00047		1	B	L01141		1	B	YC053-YC055, YC059-YD158, YL951-YR328
5573	20		CQ		1-1	33-18-37	L00047		1	B	L01141		1	B	YC056-YC058
5574	20		CQ		1-2	33-18-37	L00047		4	B	L01141		4	B	YC051-YC052
5574	20		CQ		1-3	33-18-37	L00047		4	B	L01141		4	B	YC053-YC055, YC059-YD158, YL951-YR328
5574	20		CQ		1-1	33-18-37	L00047		4	B	L01141		4	B	YC056-YC058
5575	20		CQ		3-9	33-18-37	L01141		4	B	GD00501	DC..	1A		YC051-YC052, YC056-YC058

WIRE LIST

D280A108

91-21-11

Section W2500

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To					
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W2508	286A2508				P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)											
5575	20		CQ		3-10	33-18-37	L01141		4	B	*	GD00501	DC..	1A		YC053-YC055, YC059-YD158, YL951-YR328
5576	20		CQ		5-3	33-18-37	L00001		3	B		TB0503Z	B001	1A		YC051-YC052
5576	20		CQ		7-9	33-18-37	L00001		3	B		TB0508Y	A007	1A		YC053-YC058
5576	20		CQ		6-11	33-18-37	L00001		3	B		TB0508Y	A007	1A		YC059-YD157
5576	20		CQ		6-11	33-18-37	L00001		3	B	*	TB0508Y	A007	1A		YD158, YL951-YR328
5577	20		CQ		3-6	33-18-37	L00001		3	B	*	L00019	3	B		YD158, YL951-YR328
5578	20		CQ		5-4	33-18-37	L00001		4	B		TB0505Y	B009	1A		YC051-YC052
5578	20		CQ		6-0	33-18-37	L00001		4	B		TB0505Y	B009	1A		YC053-YC058
5578	20		CQ		6-1	33-18-37	L00001		4	B		TB0505Y	B009	1A		YC059-YC064
5578	20		CQ		6-5	33-18-37	L00001		4	B		TB0505Y	B009	1A		YC065-YD157
5578	20		CQ		3-6	33-18-37	L00001		4	B		L00019	4	B	*	YD158
5578	20		CQ		3-6	33-18-37	L00001		4	B	*	L00019	4	B	*	YL951-YR328
5579	20		CQ		5-4	33-18-37	L00001		2	B		TB0505Y	A009	1A		YC051-YC052
5579	20		CQ		6-0	33-18-37	L00001		2	B		TB0505Y	A009	1A		YC053-YC058
5579	20		CQ		6-1	33-18-37	L00001		2	B		TB0505Y	A009	1A		YC059-YC064
5579	20		CQ		6-5	33-18-37	L00001		2	B		TB0505Y	A009	1A		YC065-YD157
5579	20		CQ		3-6	33-18-37	L00001		2	B		L00019	2	B	*	YD158
5579	20		CQ		3-6	33-18-37	L00001		2	B	*	L00019	2	B	*	YL951-YR328
5580	20		CQ		7-5	33-18-37	L00019		4	B	*	TB0505Y	B009	1A		YD158, YL951-YR328
5581	20		CQ		7-5	33-18-37	L00019		2	B	*	TB0505Y	A009	1A		YD158, YL951-YR328
5582	20		CQ		4-4	33-18-37	TB0505Y		B009	1A		D40550P	2			YC051-YC052
5582	20		CQ		6-11	33-18-37	TB0505Y		B009	1A		D40550P	2			YC053-YC058
5582	20		CQ		6-10	33-18-37	TB0505Y		B009	1A		D40550P	2			YC059-YC064
5582	20		CQ		4-5	33-18-37	TB0505Y		B009	1A		D40550P	2			YC065-YD158, YL951-YR328
5583	20		CQ		4-4	33-18-37	TB0505Y		A009	1A		D40550P	43			YC051-YC052
5583	20		CQ		6-11	33-18-37	TB0505Y		A009	1A		D40550P	43			YC053-YC058
5583	20		CQ		6-10	33-18-37	TB0505Y		A009	1A		D40550P	43			YC059-YC064
5583	20		CQ		4-5	33-18-37	TB0505Y		A009	1A		D40550P	43			YC065-YD158, YL951-YR328
5584	20		CQ		3-6	33-18-41	D02171		18			TB0505Y	A009	1A		YC051-YC052, YC065-YD158, YL951-YR328
5584	20		CQ		3-5	33-18-41	D02171		18			TB0505Y	A009	1A		YC053-YC058
5584	20		CQ		3-7	33-18-41	D02171		18			TB0505Y	A009	1A		YC059-YC064

WIRE LIST

D280A108

91-21-11

Section W2500

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2508	286A2508				P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)										
5585	20		CQ		3-6	33-18-41	D02173	18			TB0505Y	A009	1A		YC051-YC052, YC065-YD158, YL951-YR328
5585	20		CQ		3-5	33-18-41	D02173	18			TB0505Y	A009	1A		YC053-YC058
5585	20		CQ		3-7	33-18-41	D02173	18			TB0505Y	A009	1A		YC059-YC064
5586	20		CQ		3-6	33-18-41	D02171	3			TB0505Y	B009	1A		YC051-YC052, YC065-YD158, YL951-YR328
5586	20		CQ		3-5	33-18-41	D02171	3			TB0505Y	B009	1A		YC053-YC058
5586	20		CQ		3-7	33-18-41	D02171	3			TB0505Y	B009	1A		YC059-YC064
5587	20		CQ		3-5	33-18-41	D02171	10			TB0503Z	B001	1A		YC051-YC052, YC059-YC064
5587	20		CQ		3-4	33-18-41	D02171	10			TB0503Z	B001	1A		YC053-YC058
5587	20		CQ		3-3	33-18-41	D02171	10			TB0503Z	B001	1A		YC065-YD158, YL951-YR328
5588	20		CQ		3-5	33-18-41	D02173	10			TB0503Z	B001	1A		YC051-YC052
5588	20		CQ		3-3	33-18-41	D02173	10			TB0503Z	B001	1A		YC053-YC058, YC065-YD158, YL951-YR328
5588	20		CQ		3-6	33-18-41	D02173	10			TB0503Z	B001	1A		YC059-YC064
5589	20		CQ		3-6	33-18-41	D02169	11			TB0503Z	A001	1A		YC051-YC052
5589	20		CQ		3-5	33-18-41	D02169	11			TB0503Z	A001	1A		YC053-YC064
5589	20		CQ		3-2	33-18-41	D02169	11			TB0503Z	A001	1A		YC065-YD158, YL951-YR328
5590	20		CQ		3-4	33-18-41	D02183	11			TB0503Z	A001	1A		YC051-YC052, YC065-YD158, YL951-YR328
5590	20		CQ		3-3	33-18-41	D02183	11			TB0503Z	A001	1A		YC053-YC058
5590	20		CQ		3-7	33-18-41	D02183	11			TB0503Z	A001	1A		YC059-YC064
5591	20		CQ		5-5	33-18-41	D00650	36			D40550P	41			YC051-YC052
5591	20		CQ		8-0	33-18-41	D00650	36			D40550P	41			YC053-YC058
5591	20		CQ		7-11	33-18-41	D00650	36			D40550P	41			YC059-YC064
5591	20		CQ		5-4	33-18-41	D00650	36			D40550P	41			YC065-YD158, YL951-YR328
5592	20		CQ		3-5	33-18-41	D00650	35			TB0501Y	A013	1A		YC051-YC052
5592	20		CQ		3-4	33-18-41	D00650	35			TB0501Y	A013	1A		YC053-YC058
5592	20		CQ		3-6	33-18-41	D00650	35			TB0501Y	A013	1A		YC059-YD158, YL951-YR328
5593	20		CQ		3-9	33-18-42	D02952	5			TB0502Z	A013	1A		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W2500

Page 18

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2508	286A2508			P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)											
5593	20		CQ		3-5	33-18-42	D02952			5	TB0502Y	A009	1A		YC053-YC058
5593	20		CQ		3-7	33-18-42	D02952			5	TB0502Y	A009	1A		YC059-YD158, YL951-YR328
5594	20		CQ		3-4	33-18-42	D03172			5	TB0503Z	A009	1A		YC051-YC052
5594	20		CQ		3-5	33-18-42	D03172			5	TB0506Z	B001	1A		YC053-YC058
5594	20		CQ		3-6	33-18-42	D03172			5	TB0506Z	B001	1A		YC059-YC064
5594	20		CQ		3-4	33-18-42	D03172			5	TB0506Z	B001	1A		YC065-YD158, YL951-YR328
5595	20		CQ		3-7	33-18-42	D00440			5	TB0506Z	A001	1A		YC051-YC052, YC056-YC058
5595	20		CQ		3-5	33-18-42	D00440			5	TB0506Z	A001	1A		YC053-YC055
5595	20		CQ		3-6	33-18-42	D00440			5	TB0506Z	A001	1A		YC059-YC064
5595	20		CQ		3-4	33-18-42	D00440			5	TB0506Z	A001	1A		YC065-YD158, YL951-YR328
5596	20		CQ		1-8	33-18-42	D00440			8	GD00508	DC..	1A		YC051-YC055, YC059-YD158, YL951-YR328
5596	20		CQ		1-10	33-18-42	D00440			8	GD00508	DC..	1A		YC056-YC058
5597	20		CQ		3-7	33-18-42	D00440			7	TB0502Z	B001	1A		YC051-YC052
5597	20		CQ		3-5	33-18-42	D00440			7	TB0502Z	A001	1A		YC053-YC055
5597	20		CQ		3-7	33-18-42	D00440			7	TB0502Z	A001	1A		YC056-YC058
5597	20		CQ		3-6	33-18-42	D00440			7	TB0502Z	A001	1A		YC059-YD158, YL951-YR328
5598	20		CQ		3-9	33-18-42	D02952			7	TB0502Y	A011	1A		YC051-YC052
5598	20		CQ		3-5	33-18-42	D02952			7	TB0502Y	A011	1A		YC053-YC058
5598	20		CQ		3-7	33-18-42	D02952			7	TB0502Y	A011	1A		YC059-YD158, YL951-YR328
5599	20		CQ		2-6	33-18-42	TB0502Y	A011	1A		TB0503Z	A001	1A		YC051-YC052
5599	20		CQ		2-2	33-18-42	TB0502Y	A011	1A		TB0503Z	A001	1A		YC053-YC058
5599	20		CQ		2-4	33-18-42	TB0502Y	A011	1A		TB0503Z	A001	1A		YC059-YC064
5599	20		CQ		2-8	33-18-42	TB0502Y	A011	1A		TB0503Z	A001	1A		YC065-YD158, YL951-YR328
5600	20		CQ		3-9	33-18-42	D00483			22	TB0502Y	A011	1A		YC051-YC052
5600	20		CQ		3-5	33-18-42	D00483			22	TB0502Y	A011	1A		YC053-YC058
5600	20		CQ		3-7	33-18-42	D00483			22	TB0502Y	A011	1A		YC059-YD158, YL951-YR328
5601	20		CQ		3-9	33-18-42	D00483			19	TB0506Z	A001	1A		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W2500

Page 19

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY	Fam FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W2508	286A2508	P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)			
5601	20 CQ	3-6 33-18-42	D00483 19	TB0506Z A001 1A	YC053-YC058, YC065-YD158, YL951-YR328
5601	20 CQ	3-8 33-18-42	D00483 19	TB0506Z A001 1A	YC059-YC064
5602	20 CQ	2-0 33-18-42	D00483 23	GD00508 DC.. 1A	YC051-YC052, YC059-YD158, YL951-YR328
5602	20 CQ	1-11 33-18-42	D00483 23	GD00508 DC.. 1A	YC053-YC058
5603	20 CQ	2-3 33-18-36	D03998 22	GD00504 DC.. 1A	YC051-YC052
5603	20 CQ	2-1 33-18-36	D03998 22	GD00518 DC.. 1A	YC053-YD158, YL951-YL999, YR301-YR328
5610	20 CQ	1-8 33-14-12	D40550P 3	SM00001 W	YC051-YC052
5610	20 CQ	1-7 33-14-12	D40550P 3	SM00001 W	YC053-YD158, YL951-YR328
5611	22 PA	28-6 21-25-11	D00680 46	D46108P 1	YC051-YC052
5611	22 PA	28-7 21-25-11	D00680 46	D46108P 1	YC053-YC058
5611	22 PA	28-8 21-25-11	D00680 46	D46108P 1	YC059-YD158, YL951-YR328
5613	20 CQ	6-10 33-14-12	L00273 =G C	GD00261 DC.. 1A	YC051-YC052
5613	20 CQ	6-8 33-14-12	L00273 =G C	GD00261 DC.. 1A	YC053-YC064
5613	20 CQ	7-2 33-14-12	L00273 =G C	GD00261 DC.. 1A	YC065-YD158, YL951-YR328
5614	24 B6	28-8 21-43-21	D00646 30	D46108P 5	YC051-YC052
5614	24 B6	28-5 21-43-21	D00646 30	D46108P 5	YC053-YC058
5614	24 B6	28-6 21-43-21	D00646 30	D46108P 5	YC059-YD158, YL951-YR328
5615	24 B6	28-6 21-43-21	D00680 51	D46108P 6	YC051-YC052
5615	24 B6	28-7 21-43-21	D00680 51	D46108P 6	YC053-YC058
5615	24 B6	28-8 21-43-21	D00680 51	D46108P 6	YC059, YC065-YD158, YL951-YR328
5615	24 B6	28-8 21-43-21	D00680 51	SP04602 9	YC060-YC064
5616	24 B6	28-6 21-43-21	D00680 53	D46108P 7	YC051-YC052
5616	24 B6	28-7 21-43-21	D00680 53	D46108P 7	YC053-YC058
5616	24 B6	28-8 21-43-21	D00680 53	D46108P 7	YC059, YC065-YD158
5616	24 B6	28-8 21-43-21	D00680 53	D48106P A01	YC060-YC064
5616	24 B6	21-8 21-43-21	D00680 53	D48106P A01	YL951-YR328
5617	24 B6	21-7 21-43-21	D00680 54	D48106P A01	YC051-YC058

WIRE LIST

D280A108

91-21-11

Section W2500

Page 20

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2508		286A2508			P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)											
5617		24		B6		21-8	21-43-21	D00680		54		D48106P	A01			YC059, YC065-YD158
5617		24		B6		21-8	21-43-21	D00680		54		D00680	36			YC060-YC064
5617		24		B6		0-7	21-43-21	D00680		54		D00680	36			YL951-YR328
5618		24		B6		21-7	21-43-21	D00680		52		D48106P	A02			YC051-YC058
5618		24		B6		21-8	21-43-21	D00680		52		D48106P	A02			YC059, YC065-YD158
5618		24		B6		21-8	21-43-21	D00680		52		D00680	48			YC060-YC064
5619		20		PA		2-7	21-51-11	D00646		4		GD00504	DC..	1A		YC051-YC052
5619		20		PA		2-3	21-51-11	D00646		4		GD00518	DC..	1A		YC053-YD158,
																YL951-YR328
5620		20		CQ		1-4	33-18-42	L01001		3	B	L00481	3	B	*	YC051-YC052
5620		20		CQ		1-5	33-18-42	L01001		3	B	L00481	3	B	*	YC053-YC058
5620		20		CQ		1-6	33-18-42	L01001		3	B	L00481	3	B	*	YC059-YD158,
																YL951-YR328
5621		20		CQ		4-8	33-18-42	L01001		1	B	TB0502Z	A013	1A		YC051-YC052
5621		20		CQ		4-7	33-18-42	L01001		1	B	TB0502Y	A009	1A		YC053-YC058
5621		20		CQ		4-9	33-18-42	L01001		1	B	TB0502Y	A009	1A		YC059-YC064
5621		20		CQ		5-1	33-18-42	L01001		1	B	TB0502Y	A009	1A		YC065-YD158,
																YL951-YR328
5622		20		CQ		1-4	33-18-42	L01001		1	B	L00481	1	B	*	YC051-YC052
5622		20		CQ		1-5	33-18-42	L01001		1	B	L00481	1	B	*	YC053-YC058
5622		20		CQ		1-6	33-18-42	L01001		1	B	L00481	1	B	*	YC059-YD158,
																YL951-YR328
5623		20		CQ		1-4	33-18-42	L01001		4	B	L00481	4	B	*	YC051-YC052
5623		20		CQ		1-5	33-18-42	L01001		4	B	L00481	4	B	*	YC053-YC058
5623		20		CQ		1-6	33-18-42	L01001		4	B	L00481	4	B	*	YC059-YD158,
																YL951-YR328
5624		20		CQ		1-3	33-18-42	L00481		1	B	L00482	1	B		YC051-YC058
5624		20		CQ		1-4	33-18-42	L00481		1	B	L00482	1	B		YC059-YD158,
																YL951-YR328
5625		20		CQ		1-3	33-18-42	L00481		3	B	L00482	3	B	*	YC051-YC058
5625		20		CQ		1-4	33-18-42	L00481		3	B	L00482	3	B	*	YC059-YD158,
																YL951-YR328
5626		20		CQ		4-8	33-18-42	L00482		3	B	TB0502Y	A011	1A		YC051-YC052
5626		20		CQ		4-5	33-18-42	L00482		3	B	TB0502Y	A011	1A		YC053-YC058
5626		20		CQ		4-6	33-18-42	L00482		3	B	TB0502Y	A011	1A		YC059-YC064
5626		20		CQ		4-11	33-18-42	L00482		3	B	TB0502Y	A011	1A		YC065-YD158,
																YL951-YR328
5627		20		CQ		1-3	33-18-42	L00481		4	B	L00482	4	B	*	YC051-YC058

WIRE LIST

D280A108

91-21-11

Section W2500

Page 21

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2508	286A2508			P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)											
5627	20		CQ		1-4	33-18-42	L00481	4	B	*	L00482	4	B	*	YC059-YD158, YL951-YR328
5628	20		CQ		2-1	33-18-42	L00482	4	B	*	GD00509	DC..	1A		YC051-YC052
5628	20		CQ		2-2	33-18-42	L00482	4	B	*	GD00509	DC..	1A		YC053-YD158, YL951-YR328
5629	20		CQ		4-8	33-18-42	D02952	15			GD00264	DC..	1A		YC051-YC052
5629	20		CQ		7-6	33-18-42	D02952	15			GD00264	DC..	1A		YC053-YC058
5629	20		CQ		7-5	33-18-42	D02952	15			GD00264	DC..	1A		YC059-YC064
5629	20		CQ		4-10	33-18-42	D02952	15			GD00264	DC..	1A		YC065-YD158, YL951-YR328
5630	20		CQ		4-7	33-18-42	D03172	9			GD00264	DC..	1A		YC051-YC052
5630	20		CQ		7-5	33-18-42	D03172	9			GD00264	DC..	1A		YC053-YC058
5630	20		CQ		7-3	33-18-42	D03172	9			GD00264	DC..	1A		YC059-YC064
5630	20		CQ		4-8	33-18-42	D03172	9			GD00264	DC..	1A		YC065-YD158, YL951-YR328
5631	20		CQ		4-8	33-18-42	D02952	9			GD00264	DC..	1A		YC051-YC052
5631	20		CQ		7-6	33-18-42	D02952	9			GD00264	DC..	1A		YC053-YC058
5631	20		CQ		7-5	33-18-42	D02952	9			GD00264	DC..	1A		YC059-YC064
5631	20		CQ		4-10	33-18-42	D02952	9			GD00264	DC..	1A		YC065-YD158, YL951-YR328
5632	20		CQ		3-1	33-18-35	D00482	7			GD00504	DC..	1A		YC051-YC052
5632	20		CQ		3-0	33-18-35	D00482	7			GD00518	DC..	1A		YC053-YC055
5632	20		CQ		3-2	33-18-35	D00482	7			GD00518	DC..	1A		YC056-YC058
5632	20		CQ		2-11	33-18-35	D00482	7			GD00518	DC..	1A		YC059-YD158, YL951-YR328
5637	24		B6		4-6	21-51-11	TB0504Y	A001	1A		D40550P	26			YC051-YC052
5637	24		B6		6-11	21-51-11	TB0504Y	A001	1A		D40550P	26			YC053-YC058
5637	24		B6		6-10	21-51-11	TB0504Y	A001	1A		D40550P	26			YC059-YC064
5637	24		B6		4-5	21-51-11	TB0504Y	A001	1A		D40550P	26			YC065-YD158, YL951-YL999, YR301-YR328
5638	24		B6		36-2	21-51-11	TB0504Y	A001	1A		D40554P	A02			YC051-YC052
5638	24		B6		36-0	21-51-11	TB0504Y	A001	1A		D40554P	A02			YC053-YC055
5638	24		B6		35-9	21-51-11	TB0504Y	A001	1A		D40554P	A02			YC056-YC058
5638	24		B6		35-8	21-51-11	TB0504Y	A001	1A		D40554P	A02			YC059-YC064
5638	24		B6		35-10	21-51-11	TB0504Y	A001	1A		D40554P	A02			YC065-YD158, YL951-YL999, YR301-YR328
5640	20		CQ		3-2	33-18-42	D02889	4			TB0503Z	A009	1A		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W2500

Page 22

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice		
W2508	286A2508				P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)											
5640	20		CQ		3-4	33-18-42		D02889		4		TB0506Z	B001	1A		YC053-YC058
5640	20		CQ		3-5	33-18-42		D02889		4		TB0506Z	B001	1A		YC059-YC064
5640	20		CQ		3-8	33-18-42		D02889		4		TB0506Z	B001	1A		YC065-YD158, YL951-YR328
5641	20		CQ		3-7	33-18-42		D02889		12		TB0502Z	B001	1A		YC051-YC052
5641	20		CQ		3-4	33-18-42		D02889		12		TB0502Z	A001	1A		YC053-YC058
5641	20		CQ		3-5	33-18-42		D02889		12		TB0502Z	A001	1A		YC059-YC064
5641	20		CQ		3-10	33-18-42		D02889		12		TB0502Z	A001	1A		YC065-YD158, YL951-YR328
5642	20		CQ		3-6	23-24-11		D02889		9		TB0503Y	A025	1A		YC051-YC052
5642	20		CQ		3-5	23-24-11		D02889		9		TB0503Y	A025	1A		YC053-YC058, YC065-YD158, YL951-YR328
5642	20		CQ		3-7	23-24-11		D02889		9		TB0503Y	A025	1A		YC059-YC064
5643	22		CQ		29-1	35-11-11		D00432		1		D40556J	12			YC051-YC052
5643	22		CQ		29-0	35-11-11		D00432		1		D40556J	12			YC053-YC058
5643	22		CQ		28-11	35-11-11		D00432		1		D40556J	12			YC059-YC064
5643	22		CQ		28-10	35-11-11		D00432		1		D40556J	12			YC065-YD158, YL951-YR328
5644	20		CQ		1-10	35-11-11		D00432		2		GD00508	DC..	1A		YC051-YD158, YL951-YR328
5645	22		CQ		28-11	35-21-11		D00440		3		D40556J	18			YC051-YC052
5645	22		CQ		28-10	35-21-11		D00440		3		D40556J	18			YC053-YC055
5645	22		CQ		29-0	35-21-11		D00440		3		D40556J	18			YC056-YC058
5645	22		CQ		28-9	35-21-11		D00440		3		D40556J	18			YC059-YD158, YL951-YR328
5646	20		CQ		1-8	35-21-11		D00440		4		GD00508	DC..	1A		YC051-YC055, YC059-YD158, YL951-YR328
5646	20		CQ		1-10	35-21-11		D00440		4		GD00508	DC..	1A		YC056-YC058
5647	22		CQ		1-9	35-21-11		D00440		9		D00483	24			YC051-YC055
5647	22		CQ		1-11	35-21-11		D00440		9		D00483	24			YC056-YC058
5647	22		CQ		1-10	35-21-11		D00440		9		D00483	24			YC059-YD158, YL951-YR328
5648	20		CQ		28-11	35-21-11		D00440		6		D40556J	19			YC051-YC052
5648	20		CQ		28-10	35-21-11		D00440		6		D40556J	19			YC053-YC055
5648	20		CQ		29-0	35-21-11		D00440		6		D40556J	19			YC056-YC058
5648	20		CQ		28-9	35-21-11		D00440		6		D40556J	19			YC059-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W2500

Page 23

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W2508	286A2508				P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)											
5654	20		CQ		3-6	33-18-42	L01331		1	B	*	TB0503Z	A009	1A		YC051-YC052
5654	20		CQ		3-11	33-18-42	L01331		1	B	*	TB0506Z	B001	1A		YC053-YC058
5654	20		CQ		4-0	33-18-42	L01331		1	B	*	TB0506Z	B001	1A		YC059-YC064
5654	20		CQ		4-3	33-18-42	L01331		1	B	*	TB0506Z	B001	1A		YC065-YD158, YL951-YR328
5655	20		CQ		1-3	33-18-42	L01331		4	B		GD00509	DC..	1A		YC051-YC052
5655	20		CQ		0-10	33-18-42	L01331		4	B		GD00509	DC..	1A		YC053-YD158, YL951-YR328
5656	20		CQ		3-10	33-18-42	L01331		3	B		TB0502Z	B001	1A		YC051-YC052
5656	20		CQ		3-11	33-18-42	L01331		3	B		TB0502Z	A001	1A		YC053-YC058
5656	20		CQ		4-1	33-18-42	L01331		3	B		TB0502Z	A001	1A		YC059-YC064
5656	20		CQ		4-5	33-18-42	L01331		3	B		TB0502Z	A001	1A		YC065-YD158, YL951-YR328
5657	20		CQ		27-8	32-64-21	L01331		2	B	*	D46108P	21			YC051-YC052
5657	20		CQ		27-11	32-64-21	L01331		2	B	*	D46108P	21			YC053-YC058
5657	20		CQ		27-10	32-64-21	L01331		2	B	*	D46108P	21			YC059-YD158, YL951-YR328
5658	20		CQ		4-8	32-64-21	D00483		35			L01331	2	B	*	YC051-YC052
5658	20		CQ		4-10	32-64-21	D00483		35			L01331	2	B	*	YC053-YC058
5658	20		CQ		5-0	32-64-21	D00483		35			L01331	2	B	*	YC059-YC064
5658	20		CQ		5-1	32-64-21	D00483		35			L01331	2	B	*	YC065-YD158, YL951-YR328
5659	20		CQ		27-8	31-52-75	D00483		41			D46108P	25			YC051-YC052
5659	20		CQ		27-6	31-52-75	D00483		41			D46108P	25			YC053-YC058
5659	20		CQ		27-5	31-52-75	D00483		41			D46108P	25			YC059-YD158, YL951-YR328
5660	22		CQ		6-4	23-32-12	D02921		2			D40550P	20			YC051-YC052
5660	22		CQ		8-11	23-32-12	D02921		2			D40550P	20			YC053-YC058
5660	22		CQ		8-6	23-32-12	D02921		2			D40550P	20			YC059-YC064
5660	22		CQ		6-6	23-32-12	D02921		2			D40550P	20			YC065-YD157
5660	22		CQ		6-6	23-32-14	D02921		2			D40550P	20			YD158, YL951-YN260
5660	22		CQ		6-6	44-21-22	D02921		2			D40550P	20			YN501-YR328
5665	20		CQ		3-10	33-18-42	D02921		1			TB0503Z	A009	1A		YC051-YC052
5665	20		CQ		2-9	33-18-42	D02921		1			TB0507Y	A007	1A		YC053-YC058
5665	20		CQ		1-11	33-18-42	D02921		1			TB0507Y	A007	1A		YC059-YD157
5665	20		CQ		1-11	33-18-37	D02921		1			TB0507Y	A007	1A		YD158, YL951-YR328
5666	20		CQ		4-2	33-18-42	D02921		3			TB0502Z	A001	1A		YC051-YC052
5666	20		CQ		2-9	33-18-42	D02921		3			TB0507Z	A001	1A		YC053-YC058
5666	20		CQ		2-0	33-18-42	D02921		3			TB0507Z	A001	1A		YC059-YD157

WIRE LIST

D280A108

91-21-11

Section W2500

Page 24

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2508		286A2508			P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)											
5666		20		CQ		2-0	33-18-37	D02921		3		TB0507Z	A001	1A		YD158, YL951-YR328
5667		20		CQ		5-2	33-18-42	D02921		4		GD00509	DC..	1A		YC051-YC052
5667		20		CQ		6-2	33-18-42	D02921		4		GD00509	DC..	1A		YC053-YC058
5667		20		CQ		6-0	33-18-42	D02921		4		GD00509	DC..	1A		YC059-YC064
5667		20		CQ		6-1	33-18-42	D02921		4		GD00509	DC..	1A		YC065-YD157
5667		20		CQ		6-1	33-18-37	D02921		4		GD00509	DC..	1A		YD158, YL951-YR328
5668		20		CQ		4-8	33-18-37	D40550P		28		TB0502Y	A009	1A		YC051-YC052
5668		20		CQ		8-10	33-18-37	D40550P		28		TB0507Y	B005	1A		YC053-YC058
5668		20		CQ		8-4	33-18-37	D40550P		28		TB0507Y	B005	1A		YC059-YC064
5668		20		CQ		6-3	33-18-37	D40550P		28		TB0507Y	B005	1A		YC065-YD158, YL951-YR328
5670		20		CQ		26-6	32-64-21	TB0502Y	A029	1A		D46108P	22			YC051-YC052
5670		20		CQ		26-4	32-64-21	TB0502Y	A029	1A		D46108P	22			YC053-YC058
5670		20		CQ		26-2	32-64-21	TB0502Y	A029	1A		D46108P	22			YC059-YC064
5670		20		CQ		26-3	32-64-21	TB0502Y	A029	1A		D46108P	22			YC065-YD158, YL951-YR328
5671		24		B6		21-7	21-43-21	D00680		36		D48106P	B10			YC051-YC058
5671		24		B6		21-8	21-43-21	D00680		36		D48106P	B10			YC059, YC065-YD158
5672		24		B6		21-7	21-43-21	D00680		48		D48106P	B09			YC051-YC058
5672		24		B6		21-8	21-43-21	D00680		48		D48106P	B09			YC059, YC065-YD158
5672		24		B6		21-8	21-43-21	D48106P	B09			SP04602		9		YC060-YC064
5672		24		B6		0-7	21-43-21	D00680		48		D00680	52			YL951-YR328
5673		20		CQ		3-6	32-64-21	L01331	1	B	*	TB0502Y	B029	1A		YC051-YC052
5673		20		CQ		3-8	32-64-21	L01331	1	B	*	TB0502Y	B029	1A		YC053-YC058
5673		20		CQ		3-9	32-64-21	L01331	1	B	*	TB0502Y	B029	1A		YC059-YC064
5673		20		CQ		4-0	32-64-21	L01331	1	B	*	TB0502Y	B029	1A		YC065-YD158, YL951-YR328
5674		20		CQ		3-6	32-64-21	D00483		39		TB0502Y	A029	1A		YC051-YC052
5674		20		CQ		3-3	32-64-21	D00483		39		TB0502Y	A029	1A		YC053-YC058, YC065-YD158, YL951-YR328
5674		20		CQ		3-5	32-64-21	D00483		39		TB0502Y	A029	1A		YC059-YC064
5675		20		CQ		4-7	33-18-31	TB0502Z	A001	1A		TB0508Z	A001	1A		YC053-YC058
5675		20		CQ		4-1	33-18-31	TB0502Z	A001	1A		TB0508Z	A001	1A		YC059-YC064
5675		20		CQ		4-6	33-18-31	TB0502Z	A001	1A		TB0508Z	A001	1A		YC065-YD158, YL951-YR328
5676		20		CQ		6-6	33-18-31	TB0507Z	A001	1A		TB0508Z	A001	1A		YC053-YC058
5676		20		CQ		4-10	33-18-31	TB0507Z	A001	1A		TB0508Z	A001	1A		YC059-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W2500

Page 25

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number		Fam	Description		Diagram	From			To			Effectivity	
	GA	CO TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice
W2508	286A2508			P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)										
5677	20	CQ		4-7	31-52-21		TB0502Z	B001	1A		TB0508Z	B001	1A	YC053-YC058
5677	20	CQ		4-1	31-52-21		TB0502Z	B001	1A		TB0508Z	B001	1A	YC059-YC064
5677	20	CQ		4-6	31-52-21		TB0502Z	B001	1A		TB0508Z	B001	1A	YC065-YD158, YL951-YR328
5678	20	CQ		6-6	31-52-21		TB0507Z	B001	1A		TB0508Z	B001	1A	YC053-YC058
5678	20	CQ		4-10	31-52-21		TB0507Z	B001	1A		TB0508Z	B001	1A	YC059-YD158, YL951-YR328
5679	20	CQ		4-5	33-18-34		TB0502Y	B011	1A		TB0508Y	B005	1A	YC053-YC058
5679	20	CQ		3-11	33-18-34		TB0502Y	B011	1A		TB0508Y	B005	1A	YC059-YC064
5679	20	CQ		4-3	33-18-34		TB0502Y	B011	1A		TB0508Y	B005	1A	YC065-YD158, YL951-YR328
5680	20	CQ		4-3	33-18-33		TB0502Y	A009	1A		TB0507Y	B007	1A	YC053-YC058
5680	20	CQ		3-11	33-18-33		TB0502Y	A009	1A		TB0507Y	B007	1A	YC059-YC064
5680	20	CQ		4-4	33-18-33		TB0502Y	A009	1A		TB0507Y	B007	1A	YC065-YD158, YL951-YR328
5681	20	CQ		4-1	33-18-32		TB0503Z	A001	1A		TB0507Y	A005	1A	YC053-YC058
5681	20	CQ		3-9	33-18-32		TB0503Z	A001	1A		TB0507Y	A005	1A	YC059-YC064
5681	20	CQ		3-10	33-18-32		TB0503Z	A001	1A		TB0507Y	A005	1A	YC065-YD158, YL951-YR328
5682	20	CQ		6-5	33-18-32		TB0508Y	A005	1A		TB0507Y	A005	1A	YC053-YC058
5682	20	CQ		4-8	33-18-32		TB0508Y	A005	1A		TB0507Y	A005	1A	YC059-YD158, YL951-YR328
5683	20	CQ		4-3	33-18-36		TB0503Z	B001	1A		TB0508Y	A007	1A	YC053-YC058
5683	20	CQ		3-9	33-18-36		TB0503Z	B001	1A		TB0508Y	A007	1A	YC059-YC064
5683	20	CQ		3-10	33-18-36		TB0503Z	B001	1A		TB0508Y	A007	1A	YC065-YD158, YL951-YR328
5684	20	CQ		4-4	33-18-33		TB0506Z	B001	1A		TB0507Y	A007	1A	YC053-YC058
5684	20	CQ		4-0	33-18-33		TB0506Z	B001	1A		TB0507Y	A007	1A	YC059-YC064
5684	20	CQ		4-3	33-18-33		TB0506Z	B001	1A		TB0507Y	A007	1A	YC065-YD158, YL951-YR328
5685	20	CQ		4-6	33-18-31		TB0506Z	A001	1A		TB0508Y	B009	1A	YC053-YC058
5685	20	CQ		4-1	33-18-31		TB0506Z	A001	1A		TB0508Y	B009	1A	YC059-YC064
5685	20	CQ		4-3	33-18-31		TB0506Z	A001	1A		TB0508Y	B009	1A	YC065-YD158, YL951-YR328
5688	20	CQ		6-5	33-18-32		TB0507Y	A011	1A		TB0508Y	A009	1A	YC053-YC058
5688	20	CQ		4-8	33-18-32		TB0507Y	A011	1A		TB0508Y	A009	1A	YC059-YD158, YL951-YR328
5701	20	CQ		4-4	31-52-21		D40550P	11			TB0503Y	A007	1A	YC051-YC052
5701	20	CQ		9-0	31-52-21		D40550P	11			TB0508Y	B007	1A	YC053-YC058

WIRE LIST

D280A108

91-21-11

Section W2500

Page 26

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2508	286A2508				P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)										
5701	20		CQ		8-4	31-52-21	D40550P	11			TB0508Y	B007	1A		YC059-YC064
5701	20		CQ		6-3	31-52-21	D40550P	11			TB0508Y	B007	1A		YC065-YD158, YL951-YR328
5702	20		CQ		4-9	31-52-21	D00642	11			TB0503Y	A007	1A		YC051-YC052
5702	20		CQ		3-1	31-52-21	D00642	11			TB0508Y	B007	1A		YC053-YC058
5702	20		CQ		2-8	31-52-21	D00642	11			TB0508Y	B007	1A		YC059-YC064
5702	20		CQ		2-7	31-52-21	D00642	11			TB0508Y	B007	1A		YC065-YD158, YL951-YR328
5703	20		CQ		29-2	31-52-21	D02486	12			D46108P	9			YC051-YC052
5703	20		CQ		29-0	31-52-21	D02486	12			D46108P	9			YC053-YC058
5703	20		CQ		29-1	31-52-21	D02486	12			D46108P	9			YC059-YD158, YL951-YR328
5704	20		CQ		5-1	31-52-21	D00642	12			TB0502Z	B005	1A		YC051-YC052
5704	20		CQ		3-1	31-52-21	D00642	12			TB0508Z	B001	1A		YC053-YC058
5704	20		CQ		2-9	31-52-21	D00642	12			TB0508Z	B001	1A		YC059-YC064
5704	20		CQ		2-8	31-52-21	D00642	12			TB0508Z	B001	1A		YC065-YD158, YL951-YR328
5705	20		CQ		26-10	31-52-21	TB0502Z	B005	1A		D46108P	10			YC051-YC052
5705	20		CQ		26-7	31-52-21	TB0502Z	B001	1A		D46108P	10			YC053-YC058
5705	20		CQ		26-6	31-52-21	TB0502Z	B001	1A		D46108P	10			YC059-YC064
5705	20		CQ		26-8	31-52-21	TB0502Z	B001	1A		D46108P	10			YC065-YD158, YL951-YR328
5706	20		CQ		28-6	31-52-25	D00630	29			D46108P	12			YC051-YC052, YC059-YD158, YL951-YR328
5706	20		CQ		28-8	31-52-25	D00630	29			D46108P	12			YC053-YC058
5707	20		CQ		4-4	31-52-25	TB0505Y	B005	1A		D40550P	7			YC051-YC052
5707	20		CQ		8-10	31-52-25	TB0507Y	A009	1A		D40550P	7			YC053-YC058
5707	20		CQ		8-3	31-52-25	TB0507Y	A009	1A		D40550P	7			YC059-YC064
5707	20		CQ		6-2	31-52-25	TB0507Y	A009	1A		D40550P	7			YC065-YD158, YL951-YR328
5708	20		CQ		4-4	31-52-25	D00624	13			TB0505Y	B005	1A		YC051-YC052
5708	20		CQ		2-11	31-52-25	D00624	13			TB0507Y	A009	1A		YC053-YC058
5708	20		CQ		2-4	31-52-25	D00624	13			TB0507Y	A009	1A		YC059-YD158, YL951-YR328
5709	20		CQ		4-7	31-52-25	D00624	26			TB0502Z	B005	1A		YC051-YC052
5709	20		CQ		3-0	31-52-25	D00624	26			TB0507Z	B001	1A		YC053-YC058
5709	20		CQ		2-5	31-52-25	D00624	26			TB0507Z	B001	1A		YC059-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W2500

Page 27

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2508	286A2508				P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)										
5710	20		CQ		28-6	31-52-25	D00624		27		D46108P		11		YC051-YC052
5710	20		CQ		28-8	31-52-25	D00624		27		D46108P		11		YC053-YC058
5710	20		CQ		28-5	31-52-25	D00624		27		D46108P		11		YC059-YD158, YL951-YR328
5711	20		CQ		1-9	31-52-31	D00636		14		D00652		41		YC051-YC055
5711	20		CQ		1-10	31-52-31	D00636		14		D00652		41		YC056-YC058
5711	20		CQ		2-0	31-52-31	D00636		14		D00652		41		YC059-YC064
5711	20		CQ		2-1	31-52-31	D00636		14		D00652		41		YC065-YD158, YL951-YR328
5712	20		CQ		4-9	31-52-31	D00636		11		TB0502Z	B005	1A		YC051-YC052
5712	20		CQ		3-0	31-52-31	D00636		11		TB0507Z	B001	1A		YC053-YC058
5712	20		CQ		2-8	31-52-31	D00636		11		TB0507Z	B001	1A		YC059-YC064
5712	20		CQ		2-9	31-52-31	D00636		11		TB0507Z	B001	1A		YC065-YD158, YL951-YR328
5713	20		CQ		28-7	31-52-31	D00636		24		D46108P		13		YC051-YC058
5713	20		CQ		28-8	31-52-31	D00636		24		D46108P		13		YC059-YC064
5713	20		CQ		28-9	31-52-31	D00636		24		D46108P		13		YC065-YD158, YL951-YR328
5714	20		CQ		3-11	31-52-35	D00634		22		D00652		40		YC051-YC052
5714	20		CQ		2-11	31-52-35	D00634		22		D00652		40		YC053-YC055, YC059-YD158, YL951-YR328
5714	20		CQ		3-0	31-52-35	D00634		22		D00652		40		YC056-YC058
5715	20		CQ		6-4	31-52-35	D00634		21		TB0502Z	B005	1A		YC051-YC052
5715	20		CQ		4-2	31-52-35	D00634		21		TB0507Z	B001	1A		YC053-YC058
5715	20		CQ		3-8	31-52-35	D00634		21		TB0507Z	B001	1A		YC059-YD158, YL951-YR328
5716	20		CQ		29-8	31-52-35	D00634		9		D46108P		14		YC051-YC052, YC059-YD158, YL951-YR328
5716	20		CQ		29-9	31-52-35	D00634		9		D46108P		14		YC053-YC058
5717	20		CQ		5-2	31-52-41	D00626		4		TB0505Y	B005	1A		YC051-YC052
5717	20		CQ		3-9	31-52-41	D00626		4		TB0507Y	A009	1A		YC053-YC058
5717	20		CQ		3-2	31-52-41	D00626		4		TB0507Y	A009	1A		YC059-YD158, YL951-YR328
5718	20		CQ		5-5	31-52-41	D00628		14		TB0502Z	B005	1A		YC051-YC052
5718	20		CQ		3-9	31-52-41	D00628		14		TB0507Z	B001	1A		YC053-YC058
5718	20		CQ		3-3	31-52-41	D00628		14		TB0507Z	B001	1A		YC059-YC064

WIRE LIST

D280A108

91-21-11

Section W2500

Page 28

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To						
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W2508	286A2508				P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)												
5718	20		CQ		3-4	31-52-41		D00628		14			TB0507Z	B001	1A		YC065-YD158, YL951-YR328
5720	20		CQ		4-6	31-52-51		TB0502Y	B023	1A			D40550P	10			YC051-YC052
5720	20		CQ		7-0	31-52-51		TB0502Y	B023	1A			D40550P	10			YC053-YC058
5720	20		CQ		6-10	31-52-51		TB0502Y	B023	1A			D40550P	10			YC059-YC064
5720	20		CQ		4-5	31-52-51		TB0502Y	B023	1A			D40550P	10			YC065-YD158, YL951-YR328
5721	20		CQ		4-6	31-52-51		D00680		24			TB0502Y	B023	1A		YC051-YC052
5721	20		CQ		4-5	31-52-51		D00680		24			TB0502Y	B023	1A		YC053-YC058
5721	20		CQ		4-9	31-52-51		D00680		24			TB0502Y	B023	1A		YC059-YC064
5721	20		CQ		5-0	31-52-51		D00680		24			TB0502Y	B023	1A		YC065-YD158, YL951-YR328
5722	20		CQ		28-8	31-52-51		D00646		31			D46108P	15			YC051-YC052
5722	20		CQ		28-5	31-52-51		D00646		31			D46108P	15			YC053-YC058
5722	20		CQ		28-6	31-52-51		D00646		31			D46108P	15			YC059-YD158, YL951-YR328
5723	20		CQ		0-7	31-52-51		TB0502Z	B005	1A			TB0502Z	A005	1A		YC051-YC052
5724	20		CQ		4-8	31-52-51		D00680		35			TB0502Z	A005	1A		YC051-YC052
5724	20		CQ		2-10	31-52-51		D00680		35			TB0508Z	B001	1A		YC053-YC058
5724	20		CQ		2-6	31-52-51		D00680		35			TB0508Z	B001	1A		YC059-YD158, YL951-YR328
5725	20		CQ		4-0	31-52-55		D00644		54			TB0503Y	A007	1A		YC051-YC052
5725	20		CQ		2-4	31-52-55		D00644		54			TB0508Y	B007	1A		YC053-YC058
5725	20		CQ		2-0	31-52-55		D00644		54			TB0508Y	B007	1A		YC059-YD158, YL951-YR328
5726	20		CQ		28-2	31-52-55		D00644		57			D46108P	17			YC051-YC052
5726	20		CQ		28-0	31-52-55		D00644		57			D46108P	17			YC053-YC058
5726	20		CQ		28-3	31-52-55		D00644		57			D46108P	17			YC059-YD158, YL951-YR328
5727	20		CQ		4-4	31-52-55		D00644		11			TB0502Z	A005	1A		YC051-YC052
5727	20		CQ		2-4	31-52-55		D00644		11			TB0508Z	B001	1A		YC053-YC058
5727	20		CQ		2-1	31-52-55		D00644		11			TB0508Z	B001	1A		YC059-YD158, YL951-YR328
5728	20		CQ		3-7	31-52-61		D02952		1			TB0502Y	B023	1A		YC051-YC052
5728	20		CQ		3-5	31-52-61		D02952		1			TB0502Y	B023	1A		YC053-YC058, YC065-YD158, YL951-YR328
5728	20		CQ		3-6	31-52-61		D02952		1			TB0502Y	B023	1A		YC059-YC064
5729	20		CQ		27-8	31-52-61		D02952		2			D46108P	18			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W2500

Page 29

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2508	286A2508				P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)										
5729	20		CQ		27-6	31-52-61	D02952		2		D46108P		18		YC053-YC058
5729	20		CQ		27-5	31-52-61	D02952		2		D46108P		18		YC059-YD158, YL951-YR328
5730	20		CQ		3-9	31-52-61	D02952		3		TB0502Z	A005	1A		YC051-YC052
5730	20		CQ		3-6	31-52-61	D02952		3		TB0502Z	B001	1A		YC053-YC058
5730	20		CQ		3-8	31-52-61	D02952		3		TB0502Z	B001	1A		YC059-YD158, YL951-YR328
5731	20		CQ		5-0	31-52-65	D00482		8		TB0503Y	A007	1A		YC051-YC052
5731	20		CQ		3-5	31-52-65	D00482		8		TB0508Y	B007	1A		YC053-YC055
5731	20		CQ		3-7	31-52-65	D00482		8		TB0508Y	B007	1A		YC056-YC058
5731	20		CQ		2-11	31-52-65	D00482		8		TB0508Y	B007	1A		YC059-YD158, YL951-YR328
5732	20		CQ		29-3	31-52-65	D00482		9		D46108P		19		YC051-YC052
5732	20		CQ		29-2	31-52-65	D00482		9		D46108P		19		YC053-YC055, YC059-YD158, YL951-YR328
5732	20		CQ		29-4	31-52-65	D00482		9		D46108P		19		YC056-YC058
5733	20		CQ		5-5	31-52-65	D00482		10		TB0502Z	A005	1A		YC051-YC052
5733	20		CQ		3-5	31-52-65	D00482		10		TB0508Z	B001	1A		YC053-YC055
5733	20		CQ		3-7	31-52-65	D00482		10		TB0508Z	B001	1A		YC056-YC058
5733	20		CQ		3-0	31-52-65	D00482		10		TB0508Z	B001	1A		YC059-YD158, YL951-YR328
5734	20		CQ		6-0	31-52-75	D00483		29		D40550P		4		YC051-YC052
5734	20		CQ		8-0	31-52-75	D00483		29		D40550P		4		YC053-YC064
5734	20		CQ		5-5	31-52-75	D00483		29		D40550P		4		YC065-YD158, YL951-YR328
5735	20		CQ		27-8	31-52-75	D00483		30		D46108P		20		YC051-YC052
5735	20		CQ		27-6	31-52-75	D00483		30		D46108P		20		YC053-YC058
5735	20		CQ		27-5	31-52-75	D00483		30		D46108P		20		YC059-YD158, YL951-YR328
5736	20		CQ		3-9	31-52-75	D00483		26		TB0502Z	A005	1A		YC051-YC052
5736	20		CQ		3-6	31-52-75	D00483		26		TB0502Z	B001	1A		YC053-YC058
5736	20		CQ		3-8	31-52-75	D00483		26		TB0502Z	B001	1A		YC059-YD158, YL951-YR328
5737	20		CQ		4-2	31-52-32	D00722		18		D01086		38		YC051-YC052
5737	20		CQ		3-2	31-52-32	D00722		18		D01086		38		YC053-YC064
5737	20		CQ		3-3	31-52-32	D00722		18		D01086		38		YC065-YD158, YL951-YR328
5738	20		CQ		4-2	31-52-32	D00722		17		D01086		39		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W2500

Page 30

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice		
W2508	286A2508				P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)											
5738	20		CQ		3-2	31-52-32		D00722	17			D01086	39			YC053-YC064
5738	20		CQ		3-3	31-52-32		D00722	17			D01086	39			YC065-YD158, YL951-YR328
5739	20		CQ		4-2	31-52-32		D00730	8			D00636	29			YC051-YC052
5739	20		CQ		3-2	31-52-32		D00730	8			D00636	29			YC053-YC064
5739	20		CQ		3-3	31-52-32		D00730	8			D00636	29			YC065-YD158, YL951-YR328
5740	20		CQ		4-2	31-52-32		D00730	19			D00636	28			YC051-YC052
5740	20		CQ		3-2	31-52-32		D00730	19			D00636	28			YC053-YC064
5740	20		CQ		3-3	31-52-32		D00730	19			D00636	28			YC065-YD158, YL951-YR328
5741	20		CQ		1-8	31-52-32		D00636	22			D10596	49			YC051-YC058
5741	20		CQ		2-0	31-52-32		D00636	22			D10596	49			YC059-YC064
5741	20		CQ		2-1	31-52-32		D00636	22			D10596	49			YC065-YD158, YL951-YR328
5742	20		CQ		1-8	31-52-32		D00636	23			D10596	50			YC051-YC058
5742	20		CQ		2-0	31-52-32		D00636	23			D10596	50			YC059-YC064
5742	20		CQ		2-1	31-52-32		D00636	23			D10596	50			YC065-YD158, YL951-YR328
5743	20		CQ		2-4	31-52-56		D00638	60			D00648	27			YC051-YC052
5743	20		CQ		2-3	31-52-56		D00638	60			D00648	27			YC053-YC058
5743	20		CQ		2-2	31-52-56		D00638	60			D00648	27			YC059-YC064
5743	20		CQ		2-1	31-52-56		D00638	60			D00648	27			YC065-YD158, YL951-YR328
5744	20		CQ		2-4	31-52-56		D00644	60			D00462	10			YC051-YC052, YC065-YD158, YL951-YR328
5744	20		CQ		2-3	31-52-56		D00644	60			D00462	10			YC053-YC064
5745	20		CQ		3-0	33-18-35		D02486	11			GD00504	DC..	1A		YC051-YC052
5745	20		CQ		2-10	33-18-35		D02486	11			GD00518	DC..	1A		YC053-YD158, YL951-YR328
5747	20		CQ		28-6	31-52-51		D00680	37			D46108P	16			YC051-YC052
5747	20		CQ		28-7	31-52-51		D00680	37			D46108P	16			YC053-YC058
5747	20		CQ		28-8	31-52-51		D00680	37			D46108P	16			YC059-YD158, YL951-YL999, YR301-YR328
6006	20		CQ		5-3	28-21-11		D00626	32			TB0504Y	B005	1A		YC051-YC064
6006	20		CQ		6-1	28-21-11		D00626	32			TB0504Y	B005	1A		YC065-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W2500

Page 31

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2508	286A2508				P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)										
6007	20		CQ		7-0	28-21-11	D00626		23		TB0261Y	B011	1A		YC051-YC052
6007	20		CQ		9-2	28-21-11	D00626		23		TB0261Y	B011	1A		YC053-YC058
6007	20		CQ		9-0	28-21-11	D00626		23		TB0261Y	B011	1A		YC059-YC064
6007	20		CQ		7-3	28-21-11	D00626		23		TB0261Y	B011	1A		YC065-YD158, YL951-YR328
6008	20		CQ		7-0	28-21-11	D00626		29		TB0261Y	B005	1A		YC051-YC052
6008	20		CQ		9-2	28-21-11	D00626		29		TB0261Y	B005	1A		YC053-YC058
6008	20		CQ		9-0	28-21-11	D00626		29		TB0261Y	B005	1A		YC059-YC064
6008	20		CQ		7-3	28-21-11	D00626		29		TB0261Y	B005	1A		YC065-YD158, YL951-YR328
6009	20		CQ		7-1	28-21-11	D00626		30		TB0261X	B004	1A		YC051-YC052
6009	20		CQ		9-1	28-21-11	D00626		30		TB0261X	B004	1A		YC053-YC058
6009	20		CQ		8-11	28-21-11	D00626		30		TB0261X	B004	1A		YC059-YC064
6009	20		CQ		7-3	28-21-11	D00626		30		TB0261X	B004	1A		YC065-YD158, YL951-YR328
6010	20		CQ		3-7	28-21-11	D00626		22		GD00503	DC..	1A		YC051-YC052
6010	20		CQ		3-8	28-21-11	D00626		22		GD00503	DC..	1A		YC053-YC058
6010	20		CQ		3-3	28-21-11	D00626		22		GD00503	DC..	1A		YC059-YD158, YL951-YR328
6013	20		CQ		3-7	28-43-11	D00626		19		GD00503	ST..	1A		YC051-YC052
6013	20		CQ		3-8	28-43-11	D00626		19		GD00503	ST..	1A		YC053-YC058
6013	20		CQ		3-3	28-43-11	D00626		19		GD00503	ST..	1A		YC059-YD158, YL951-YR328
6015	20		CQ		17-11	28-21-11	TB0261Y		B005	1A	D48106P	A10			YC051-YC052
6015	20		CQ		18-8	28-21-11	TB0261Y		B005	1A	D48106P	A10			YC053-YC064
6015	20		CQ		19-6	28-21-11	TB0261Y		B005	1A	D48106P	A10			YC065-YD158, YL951-YR328
6016	22		CQ		21-9	30-11-11	D00648		26		D48106P	B01			YC051-YC052
6016	22		CQ		21-7	30-11-11	D00648		26		D48106P	B01			YC053-YC058, YC065-YD158, YL951-YR328
6016	22		CQ		21-8	30-11-11	D00648		26		D48106P	B01			YC059-YC064
6018	22		CQ		41-8	21-33-11	D00654		7		SP00575		W		YC060-YC064
6022	24		B6		7-8	76-21-11	D00626		3		D40550P		22		YC051-YC052
6022	24		B6		10-0	76-21-11	D00626		3		D40550P		22		YC053-YC058
6022	24		B6		9-10	76-21-11	D00626		3		D40550P		22		YC059-YC064
6022	24		B6		7-9	76-21-11	D00626		3		D40550P		22		YC065-YD158, YL951-YR328
6023	24		B6		22-5	76-21-11	D00626		27		D48106P	B08			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W2500

Page 32

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2508	286A2508			P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)											
6023	24		B6		22-6	76-21-11	D00626	27			D48106P	B08			YC053-YC058
6023	24		B6		22-4	76-21-11	D00626	27			D48106P	B08			YC059-YD158, YL951-YR328
6024	20		CQ		7-0	76-21-11	D00626	24			TB0261Y	B009	1A		YC051-YC052
6024	20		CQ		9-2	76-21-11	D00626	24			TB0261Y	B009	1A		YC053-YC058
6024	20		CQ		9-0	76-21-11	D00626	24			TB0261Y	B009	1A		YC059-YC064
6024	20		CQ		7-3	76-21-11	D00626	24			TB0261Y	B009	1A		YC065-YD158, YL951-YR328
6025	20		CQ		17-11	76-21-11	TB0261Y	A009	1A		D48106P	B07			YC051-YC052
6025	20		CQ		18-8	76-21-11	TB0261Y	A009	1A		D48106P	B07			YC053-YC064
6025	20		CQ		19-6	76-21-11	TB0261Y	A009	1A		D48106P	B07			YC065-YD158, YL951-YR328
6027	20		CQ		3-7	76-21-11	D00626	25			GD00503	DC..	1A		YC051-YC052
6027	20		CQ		3-8	76-21-11	D00626	25			GD00503	DC..	1A		YC053-YC058
6027	20		CQ		3-3	76-21-11	D00626	25			GD00503	DC..	1A		YC059-YD158, YL951-YR328
6029	24		B6		32-1	80-11-11	S00266	X1	C		D40556J	24			YC051-YC052
6029	24		B6		32-5	80-11-11	S00266	X1	C		D40556J	24			YC053-YC055
6029	24		B6		32-4	80-11-11	S00266	X1	C		D40556J	24			YC056-YD158, YL951-YR328
6030	24		B6		0-7	80-11-11	S00266	X2	C		S00266	1B	C	*	YC051-YC064, YL951-YL999, YR301-YR328
6030	24		B6		1-6	80-11-11	S00266	X2	C		S00266	1B	C	*	YC065-YD158, YN231-YN501
6031	20		CQ		32-1	80-11-11	S00266	1B	C	*	D40556J	10			YC051-YC052
6031	20		CQ		32-5	80-11-11	S00266	1B	C	*	D40556J	10			YC053-YC055
6031	20		CQ		32-4	80-11-11	S00266	1B	C	*	D40556J	10			YC056-YD158, YL951-YR328
6032	20		CQ		21-8	30-21-11	D00462	14			D48106P	B02			YC051-YC052, YC065-YD158, YL951-YR328
6032	20		CQ		21-6	30-21-11	D00462	14			D48106P	B02			YC053-YC058
6032	20		CQ		21-7	30-21-11	D00462	14			D48106P	B02			YC059-YC064
6033	22		CQ		21-8	30-21-11	D00462	13			D48106P	B05			YC051-YC052, YC065-YD158, YL951-YR328
6033	22		CQ		21-6	30-21-11	D00462	13			D48106P	B05			YC053-YC058
6033	22		CQ		21-7	30-21-11	D00462	13			D48106P	B05			YC059-YC064

WIRE LIST

D280A108

91-21-11

Section W2500

Page 33

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2508	286A2508				P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)											
8001	20		CQ		3-3		34-51-41	D00553		29		GD00503	DC..	1A		YC051-YC052
8001	20		CQ		3-2		34-51-41	D00553		29		GD00503	DC..	1A		YC053-YC058
8001	20		CQ		2-10		34-51-41	D00553		29		GD00503	DC..	1A		YC059-YD158, YL951-YR328
8002	22		CQ		22-0		34-51-41	D00553		30		D48106P	B06			YC051-YC058
8002	22		CQ		21-11		34-51-41	D00553		30		D48106P	B06			YC059-YD158, YL951-YR328
8003	20		CQ		3-3		34-51-41	D00553		28		GD00503	DC..	1A		YC051-YC052
8003	20		CQ		3-2		34-51-41	D00553		28		GD00503	DC..	1A		YC053-YC058
8003	20		CQ		2-10		34-51-41	D00553		28		GD00503	DC..	1A		YC059-YD158, YL951-YR328
8004	22		CQ		30-5		34-51-41	D00553		27		D40556J	3			YC051-YC058
8004	22		CQ		30-4		34-51-41	D00553		27		D40556J	3			YC059-YD158, YL951-YR328
8005	22		PA		30-2		34-21-15	D01817		37		D40556J	6			YC051-YC052, YC059-YD158, YL951-YR328
8005	22		PA		30-3		34-21-15	D01817		37		D40556J	6			YC053-YC058
8006	20		PA		3-0		34-21-15	D01817		36		GD00503	AC..	1A		YC051-YC058
8006	20		PA		2-8		34-21-15	D01817		36		GD00503	AC..	1A		YC059-YD158, YL951-YR328
8007	22		PA		30-5		34-21-15	D00553		43		D40556J	16			YC051-YC058
8007	22		PA		30-4		34-21-15	D00553		43		D40556J	16			YC059-YD158, YL951-YR328
8012	22		PA		30-2		34-21-15	D01817		40		D40556J	44			YC051-YC052, YC059-YD158, YL951-YR328
8012	22		PA		30-3		34-21-15	D01817		40		D40556J	44			YC053-YC058
8013	20		PA		2-9		34-21-15	D01817		39		GD00505	AC..	1A		YC051-YC052
8013	20		PA		2-8		34-21-15	D01817		39		GD00515	AC..	1A		YC053-YC058
8013	20		PA		2-7		34-21-15	D01817		39		GD00515	AC..	1A		YC059-YD158, YL951-YR328
8014	22		PA		30-5		34-21-15	D00553		40		D40556J	45			YC051-YC058
8014	22		PA		30-4		34-21-15	D00553		40		D40556J	45			YC059-YD158, YL951-YR328
8015	22		PA		30-5		34-21-15	D00553		53		D40556J	11			YC051-YC058
8015	22		PA		30-4		34-21-15	D00553		53		D40556J	11			YC059-YD158, YL951-YR328
8017	22		PA		30-5		34-21-15	D00553		45		D40556J	26			YC051-YC058

WIRE LIST

D280A108

91-21-11

Section W2500

Page 34

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				Effectivity
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W2508	286A2508				P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SA2 (continued)										
8017	22		PA		30-4	34-21-15	D00553		45		D40556J		26		YC059-YD158, YL951-YR328
8018	20		PA		3-3	34-21-15	D00553		44		GD00503	DC..	1A		YC051-YC052
8018	20		PA		3-2	34-21-15	D00553		44		GD00503	DC..	1A		YC053-YC058
8018	20		PA		2-10	34-21-15	D00553		44		GD00503	DC..	1A		YC059-YD158, YL951-YR328
FRAB					0-0	21-31-11	D10724			AB	GD00504	ST..	1A		YC051-YC052
FRAB					0-0	21-31-11	D10724			AB	GD00518	ST..	1A		YC053-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W2500

Page 35 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2510	286A2510				P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SB2										
0004	24		PK		20-8	29-33-11	D02486		7		D46126P		3		YC051-YC052
0004	24		PK		20-1	29-33-11	D02486		7		D46126P		3		YC053-YC058
0004	24		PK		20-2	29-33-11	D02486		7		D46126P		3		YC059-YR328
0101	22		CQ		31-3	21-33-11	TB0502Y	B009	1A		D46126P		32		YC060-YC064
0101	22		CQ		17-9	21-33-11	TB0502Y	B009	1A		D46126P		32		YL952-YL999, YN232-YR328
0501	24		B6		4-6	24-31-12	D01086		8		TB0504Y	A009	1A		YC051-YC052
0501	24		B6		4-5	24-31-12	D01086		8		TB0504Y	A009	1A		YC053-YC058
0501	24		B6		4-7	24-31-12	D01086		8		TB0504Y	A009	1A		YC059-YC064
0501	24		B6		5-0	24-31-12	D01086		8		TB0504Y	A009	1A		YC065-YR328
0502	24		B6		7-0	24-31-12	D01086		2		D40558P		2		YC051-YC052
0502	24		B6		6-10	24-31-12	D01086		2		D40558P		2		YC053-YC064
0502	24		B6		6-11	24-31-12	D01086		2		D40558P		2		YC065-YR328
0503	24		B6		3-11	24-31-12	TB0504Y	A009	1A		D40558P		3		YC051-YC052, YC065-YR328
0503	24		B6		3-10	24-31-12	TB0504Y	A009	1A		D40558P		3		YC053-YC058
0503	24		B6		3-9	24-31-12	TB0504Y	A009	1A		D40558P		3		YC059-YC064
0504	20		CQ		2-4	24-31-12	D00652		4		GD00505	DC..	1A		YC051-YC052
0504	20		CQ		2-3	24-31-12	D00652		4		GD00515	DC..	1A		YC053-YC058
0504	20		CQ		2-4	24-31-12	D00652		4		GD00515	DC..	1A		YC059-YR328
0505	24		B6		6-6	24-31-12	D00652		1		D40558P		11		YC051-YC052, YC059-YR328
0505	24		B6		6-5	24-31-12	D00652		1		D40558P		11		YC053-YC058
0506	24		B6		4-1	24-31-12	D00652		27		TB0504Y	A009	1A		YC051-YC052
0506	24		B6		4-0	24-31-12	D00652		27		TB0504Y	A009	1A		YC053-YC058
0506	24		B6		4-4	24-31-12	D00652		27		TB0504Y	A009	1A		YC059-YC064
0506	24		B6		4-7	24-31-12	D00652		27		TB0504Y	A009	1A		YC065-YR328
0507	24		B6		6-6	24-31-12	D00652		26		D40558P		12		YC051-YC052, YC059-YR328
0507	24		B6		6-5	24-31-12	D00652		26		D40558P		12		YC053-YC058
0508	24		B6		6-6	24-31-12	D00652		28		D40558P		13		YC051-YC052, YC059-YR328
0508	24		B6		6-5	24-31-12	D00652		28		D40558P		13		YC053-YC058
0509	22		CQ		25-6	49-62-11	S00248	1NO	B		D40560J		9		YC051-YC052
0509	22		CQ		24-11	49-62-11	S00248	1NO	B		D40560J		9		YC053-YR328
0510	22		CQ		0-7	49-62-11	S00248	1C	B		S00248	2C	B	*	ALL
0511	20		CQ		8-6	49-62-11	S00248	2C	B	*	D40558P		9		YC051-YC052
0511	20		CQ		8-3	49-62-11	S00248	2C	B	*	D40558P		9		YC053-YR328
0514	24		PK		30-6	29-34-11	D02486		6		D40562P	A14			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W2510

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2510		286A2510			P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SB2 (continued)											
0514		24		PK		29-11	29-34-11	D02486		6		D40562P		A14		YC053-YC055
0514		24		PK		29-8	29-34-11	D02486		6		D40562P		A14		YC056-YC058
0514		24		PK		29-9	29-34-11	D02486		6		D40562P		A14		YC059-YR328
0515		18		CQ		6-10	24-11-21	D00636		20	18	D40558P		10	18	YC051-YC052, YC059-YC064
0515		18		CQ		6-9	24-11-21	D00636		20	18	D40558P		10	18	YC053-YC058
0515		18		CQ		6-11	24-11-21	D00636		20	18	D40558P		10	18	YC065-YR328
0516		18		CQ		20-4	24-11-21	D00636		31	18	D46126P		21		YC051-YC052
0516		18		CQ		19-9	24-11-21	D00636		31	18	D46126P		21		YC053-YC058
0516		18		CQ		19-10	24-11-21	D00636		31	18	D46126P		21		YC059-YC064
0516		18		CQ		19-11	24-11-21	D00636		31	18	D46126P		21		YC065-YR328
0519		22		PA		30-0	27-83-21	D00630		31		D40562P		A06		YC051-YC052
0519		22		PA		29-5	27-83-21	D00630		31		D40562P		A06		YC053-YC055
0519		22		PA		29-3	27-83-21	D00630		31		D40562P		A06		YC056-YR328
2202B		24		Y2	KB	23-7	24-33-11	D00652		53		D40560J		14		YC051-YC052
2202B		24		Y2	KB	23-1	24-33-11	D00652		53		D40560J		14		YC053-YC058
2202B		24		Y2	KB	23-2	24-33-11	D00652		53		D40560J		14		YC059-YR328
2202R		24		Y2	KB	0-0	24-33-11	D00652		35		D40560J		4		ALL
2202Z					KB	0-0	24-33-11	D00652		DED		D40560J		DED		ALL
2203B		24		Y2	KC	23-7	24-33-11	D00652		52		D40560J		15		YC051-YC052
2203B		24		Y2	KC	23-1	24-33-11	D00652		52		D40560J		15		YC053-YC058
2203B		24		Y2	KC	23-2	24-33-11	D00652		52		D40560J		15		YC059-YR328
2203R		24		Y2	KC	0-0	24-33-11	D00652		34		D40560J		5		ALL
2203Z					KC	0-0	24-33-11	D00652		DED		D40560J		DED		ALL
2204B		24		Y2	KD	23-7	24-33-11	D00652		51		D40560J		16		YC051-YC052
2204B		24		Y2	KD	23-1	24-33-11	D00652		51		D40560J		16		YC053-YC058
2204B		24		Y2	KD	23-2	24-33-11	D00652		51		D40560J		16		YC059-YR328
2204R		24		Y2	KD	0-0	24-33-11	D00652		33		D40560J		6		ALL
2204Z					KD	0-0	24-33-11	D00652		DED		D40560J		DED		ALL
2601B		24		Y2	SA	30-9	76-21-21	D00628		12		D40562P		B05		YC051-YC052
2601B		24		Y2	SA	30-1	76-21-21	D00628		12		D40562P		B05		YC053-YC055
2601B		24		Y2	SA	29-11	76-21-21	D00628		12		D40562P		B05		YC056-YC064
2601B		24		Y2	SA	30-0	76-21-21	D00628		12		D40562P		B05		YC065-YR328
2601R		24		Y2	SA	0-0	76-21-21	D00628		11		D40562P		A05		ALL
2601Z					SA	0-0	76-21-21	D00628		DED		D40562P		DED		ALL
5501		24		B6		4-4	21-51-21	TB0504Y		B003	1A	D00680		13		YC051-YC052
5501		24		B6		4-5	21-51-21	TB0504Y		B003	1A	D00680		13		YC053-YC058
5501		24		B6		4-8	21-51-21	TB0504Y		B003	1A	D00680		13		YC059-YC064

WIRE LIST

D280A108

91-21-11

Section W2510

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W2510	286A2510	P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SB2 (continued)													
5501	24	B6	5-0	21-51-21	TB0504Y	B003	1A		D00680	13			YC065-YL999, YR301-YR328		
5502	22	PA	29-10	21-25-11	D00680	47			D40562P	A13			YC051-YC052		
5502	22	PA	29-5	21-25-11	D00680	47			D40562P	A13			YC053-YC055		
5502	22	PA	29-3	21-25-11	D00680	47			D40562P	A13			YC056-YC058		
5502	22	PA	29-4	21-25-11	D00680	47			D40562P	A13			YC059-YR328		
5503	24	B6	7-5	21-31-23	D10724	16			D40558P	5			YC051-YC052		
5503	24	B6	7-3	21-31-23	D10724	16			D40558P	5			YC053-YC058		
5503	24	B6	7-6	21-31-23	D10724	16			D40558P	5			YC059-YR328		
5504	20	CQ	3-2	21-31-23	D10724	29			GD00504	DC..	1A		YC051-YC052		
5504	20	CQ	2-11	21-31-23	D10724	29			GD00518	DC..	1A		YC053-YC058		
5504	20	CQ	3-2	21-31-23	D10724	29			GD00518	DC..	1A		YC059-YR328		
5505	24	B6	21-1	21-43-21	D10726	27			D46126P	2			YC051-YC052		
5505	24	B6	20-5	21-43-21	D10726	27			D46126P	2			YC053-YC058		
5505	24	B6	20-7	21-43-21	D10726	27			D46126P	2			YC059-YR328		
5506	22	CQ	3-4	21-43-21	D10726	26			GD00504	DC..	1A		YC051-YC052		
5506	22	CQ	3-1	21-43-21	D10726	26			GD00518	DC..	1A		YC053-YC058		
5506	22	CQ	3-3	21-43-21	D10726	26			GD00518	DC..	1A		YC059-YR328		
5507	24	B6	4-1	21-51-21	TB0504Y	B003	1A		D40558P	8			YC051-YC052, YC065-YL999, YR301-YR328		
5507	24	B6	4-0	21-51-21	TB0504Y	B003	1A		D40558P	8			YC053-YC058		
5507	24	B6	3-11	21-51-21	TB0504Y	B003	1A		D40558P	8			YC059-YC064		
5507	24	B6	6-9	21-51-21	D00680	13			D40558P	8			YN231-YN501		
5508	24	B6	29-10	21-51-21	D00680	42			D40562P	A02			YC051-YC052		
5508	24	B6	29-5	21-51-21	D00680	42			D40562P	A02			YC053-YC055		
5508	24	B6	29-3	21-51-21	D00680	42			D40562P	A02			YC056-YC058		
5508	24	B6	29-4	21-51-21	D00680	42			D40562P	A02			YC059-YR328		
5509	24	B6	29-10	21-51-21	D00680	45			D40562P	B02			YC051-YC052		
5509	24	B6	29-5	21-51-21	D00680	45			D40562P	B02			YC053-YC055		
5509	24	B6	29-3	21-51-21	D00680	45			D40562P	B02			YC056-YC058		
5509	24	B6	29-4	21-51-21	D00680	45			D40562P	B02			YC059-YR328		
5510	24	B6	29-10	21-51-21	D00680	29			D40562P	A03			YC051-YC052		
5510	24	B6	29-5	21-51-21	D00680	29			D40562P	A03			YC053-YC055		
5510	24	B6	29-3	21-51-21	D00680	29			D40562P	A03			YC056-YC058		
5510	24	B6	29-4	21-51-21	D00680	29			D40562P	A03			YC059-YR328		
5511	24	B6	29-10	21-51-21	D00680	30			D40562P	B03			YC051-YC052		
5511	24	B6	29-5	21-51-21	D00680	30			D40562P	B03			YC053-YC055		
5511	24	B6	29-3	21-51-21	D00680	30			D40562P	B03			YC056-YC058		

WIRE LIST

D280A108

91-21-11

Section W2510

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type
W2510	286A2510				P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SB2 (continued)									
5511	24	B6		29-4	21-51-21	D00680		30		D40562P	B03			YC059-YR328
5512	24	B6		29-10	21-51-21	D00680		41		D40562P	A04			YC051-YC052
5512	24	B6		29-5	21-51-21	D00680		41		D40562P	A04			YC053-YC055
5512	24	B6		29-3	21-51-21	D00680		41		D40562P	A04			YC056-YC058
5512	24	B6		29-4	21-51-21	D00680		41		D40562P	A04			YC059-YR328
5513	20	CQ		5-5	33-18-32	D00628		5		TB0502Z	B013	1A		YC051-YC052
5513	20	CQ		3-6	33-18-32	D00628		5		TB0507Y	A011	1A		YC053-YC055
5513	20	CQ		3-7	33-18-32	D00628		5		TB0507Y	A011	1A		YC056-YC058
5513	20	CQ		3-2	33-18-32	D00628		5		TB0507Y	A011	1A		YC059-YR328
5514	24	B6		27-9	21-51-21	TB0504Y	B003	1A		D40562P	B06			YC051-YC052
5514	24	B6		27-4	21-51-21	TB0504Y	B003	1A		D40562P	B06			YC053-YC055
5514	24	B6		27-1	21-51-21	TB0504Y	B003	1A		D40562P	B06			YC056-YC058
5514	24	B6		27-0	21-51-21	TB0504Y	B003	1A		D40562P	B06			YC059-YC064
5514	24	B6		27-2	21-51-21	TB0504Y	B003	1A		D40562P	B06			YC065-YL999, YR301-YR328
5515	24	PK		29-10	21-51-25	D00680		11		D40562P	B13			YC051-YC052
5515	24	PK		29-5	21-51-25	D00680		11		D40562P	B13			YC053-YC055
5515	24	PK		29-3	21-51-25	D00680		11		D40562P	B13			YC056-YC058
5515	24	PK		29-4	21-51-25	D00680		11		D40562P	B13			YC059-YR328
5516	24	B6		29-10	21-51-25	D00680		25		D40562P	B04			YC051-YC052
5516	24	B6		29-5	21-51-25	D00680		25		D40562P	B04			YC053-YC055
5516	24	B6		29-3	21-51-25	D00680		25		D40562P	B04			YC056-YC058
5516	24	B6		29-4	21-51-25	D00680		25		D40562P	B04			YC059-YR328
5701	20	CQ		21-0	31-52-41	D00628		4		D46126P	4			YC051-YC052
5701	20	CQ		20-4	31-52-41	D00628		4		D46126P	4			YC053-YC064
5701	20	CQ		20-5	31-52-41	D00628		4		D46126P	4			YC065-YR328
5703	20	CQ		3-4	31-52-41	D00628		16		GD00505	DC..	1A		YC051-YC052
5703	20	CQ		3-2	31-52-41	D00628		16		GD00515	DC..	1A		YC053-YC058, YC065-YR328
5703	20	CQ		3-1	31-52-41	D00628		16		GD00515	DC..	1A		YC059-YC064
6001	20	CQ		3-4	28-21-11	D00628		22		GD00505	DC..	1A		YC051-YC052
6001	20	CQ		3-2	28-21-11	D00628		22		GD00515	DC..	1A		YC053-YC058, YC065-YR328
6001	20	CQ		3-1	28-21-11	D00628		22		GD00515	DC..	1A		YC059-YC064
6002	20	CQ		6-10	28-21-11	D00628		23		TB0262Y	B011	1A		YC051-YC064
6002	20	CQ		6-11	28-21-11	D00628		23		TB0262Y	B011	1A		YC065-YR328
6003	20	CQ		6-10	28-21-11	D00628		29		TB0262Y	A005	1A		YC051-YC052, YC065-YR328
6003	20	CQ		6-8	28-21-11	D00628		29		TB0262Y	A005	1A		YC053-YC055

WIRE LIST

D280A108

91-21-11

Section W2510

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY	Description Fam FT-IN Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W2510	286A2510	P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SB2 (continued)									
6003	20	CQ	6-9	28-21-11	D00628	29	TB0262Y	A005	1A		YC056-YC064
6004	20	CQ	6-10	28-21-11	D00628	30	TB0262X	A004	1A		YC051-YC052, YC056-YC058, YC065-YR328
6004	20	CQ	6-9	28-21-11	D00628	30	TB0262X	A004	1A		YC053-YC055, YC059-YC064
6005	20	CQ	5-2	28-21-11	D00628	32	TB0504Y	B005	1A		YC051-YC052, YC059-YC064
6005	20	CQ	5-0	28-21-11	D00628	32	TB0504Y	B005	1A		YC053-YC058
6005	20	CQ	6-1	28-21-11	D00628	32	TB0504Y	B005	1A		YC065-YR328
6006	20	CQ	3-11	28-21-11	TB0504Y	B005 1A	D40558P	6			YC051-YC058
6006	20	CQ	3-10	28-21-11	TB0504Y	B005 1A	D40558P	6			YC059-YC064
6006	20	CQ	4-0	28-21-11	TB0504Y	B005 1A	D40558P	6			YC065-YR328
6007	20	CQ	7-7	28-22-11	D00628	8	D40558P	7			YC051-YC052
6007	20	CQ	7-4	28-22-11	D00628	8	D40558P	7			YC053-YC064
6007	20	CQ	7-5	28-22-11	D00628	8	D40558P	7			YC065-YR328
6013	20	CQ	3-4	28-43-11	D00628	19	GD00505	ST..	1A		YC051-YC052
6013	20	CQ	3-2	28-43-11	D00628	19	GD00515	ST..	1A		YC053-YC058, YC065-YR328
6013	20	CQ	3-1	28-43-11	D00628	19	GD00515	ST..	1A		YC059-YC064
6015	24	B6	7-7	76-21-21	D00628	3	D40558P	15			YC051-YC052
6015	24	B6	7-4	76-21-21	D00628	3	D40558P	15			YC053-YC064
6015	24	B6	7-5	76-21-21	D00628	3	D40558P	15			YC065-YR328
6016	20	CQ	3-4	76-21-21	D00628	25	GD00505	DC..	1A		YC051-YC052
6016	20	CQ	3-2	76-21-21	D00628	25	GD00515	DC..	1A		YC053-YC058, YC065-YR328
6016	20	CQ	3-1	76-21-21	D00628	25	GD00515	DC..	1A		YC059-YC064
6017	24	B6	21-0	76-21-21	D00628	27	D46126P	5			YC051-YC052
6017	24	B6	20-4	76-21-21	D00628	27	D46126P	5			YC053-YC064
6017	24	B6	20-5	76-21-21	D00628	27	D46126P	5			YC065-YR328
6018	20	CQ	16-0	76-21-21	TB0262Y	A009 1A	D46126P	6			YC051-YC052
6018	20	CQ	16-2	76-21-21	TB0262Y	A009 1A	D46126P	6			YC053-YR328
6019	20	CQ	6-10	76-21-21	D00628	24	TB0262Y	B009	1A		YC051-YC064
6019	20	CQ	6-11	76-21-21	D00628	24	TB0262Y	B009	1A		YC065-YR328
6021	20	CQ	9-4	80-11-11	S00267	1A C	D40558P	4			YC051-YC055, YC059-YR328
6021	20	CQ	9-1	80-11-11	S00267	1A C	D40558P	4			YC056-YC058
6022	24	B6	32-7	80-11-11	S00267	X1 C	D40562P	B11			YC051-YC052
6022	24	B6	32-1	80-11-11	S00267	X1 C	D40562P	B11			YC053-YC055

WIRE LIST

D280A108

91-21-11

Section W2510

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W2510	286A2510	P5 OVHD PANEL TO EE BAY (E1-4/E4-1) SB2 (continued)													
6022	24	B6	31-9	80-11-11	S00267	X1	C		D40562P	B11				YC056-YC058	
6022	24	B6	31-11	80-11-11	S00267	X1	C		D40562P	B11				YC059-YR328	
6023	24	B6	0-7	80-11-11	S00267	X2	C		S00267	1B	C	*		ALL	
6024	20	CQ	32-7	80-11-11	S00267	1B	C	*	D40562P	A12				YC051-YC052	
6024	20	CQ	32-1	80-11-11	S00267	1B	C	*	D40562P	A12				YC053-YC055	
6024	20	CQ	31-9	80-11-11	S00267	1B	C	*	D40562P	A12				YC056-YC058	
6024	20	CQ	31-11	80-11-11	S00267	1B	C	*	D40562P	A12				YC059-YR328	
6025	22	CQ	21-10	30-11-11	D00648	29			TB0606X	A004	1A			YC051-YC052	
6025	22	CQ	21-3	30-11-11	D00648	29			TB0606X	A004	1A			YC053-YC058, YC065-YR328	
6025	22	CQ	21-4	30-11-11	D00648	29			TB0606X	A004	1A			YC059-YC064	
6026	20	CQ	16-0	28-21-11	TB0262Y	A005	1A		D46126P	8				YC051-YC052	
6026	20	CQ	16-1	28-21-11	TB0262Y	A005	1A		D46126P	8				YC053-YR328	
6028	20	CQ	16-0	28-21-11	TB0262Y	A011	1A		D46126P	1				YC051-YC052	
6028	20	CQ	16-2	28-21-11	TB0262Y	A011	1A		D46126P	1				YC053-YR328	
6029	20	CQ	18-11	76-21-21	D40562P	A07			D46126P	7				YC051-YC055	
6029	20	CQ	18-9	76-21-21	D40562P	A07			D46126P	7				YC056-YR328	
6050	22	GA	9-0	24-28-41	D00652	7			D40558P	14				YC051-YD153	
6050	22	PA	6-6	24-28-41	D00652	7			D40558P	14				YD154-YR328	
6051	22	GA	5-0	24-28-41	D00652	6			GD00507	DC..	1A			YC051-YC052	
6051	22	GA	5-0	24-28-41	D00652	6			GD00519	DC..	1A			YC053-YD153	
6051	22	PA	2-5	24-28-41	D00652	6			GD00519	DC..	1A			YD154-YR328	
W2511	286A2511	HF COMM NO. 1 CONTROL PNL													
0001	20	PA	4-1	33-11-41	D00419	1			TB0801W	A013	1			YC051-YD157	
0002	20	PA	3-11	33-11-41	D00419	2			GD00815	AC..	1A			YC051-YD157	
0003	20	CQ	17-10	23-11-11	D00419	3			D08511P	A01				YC051-YC052	
0003	20	CQ	18-5	23-11-11	D00419	3			D08511P	A01				YC053-YD157	
0004	20	PA	3-11	23-11-11	D00419	4			GD00815	AC..	1A			YC051-YD157	
0005	24	PK	17-10	23-11-11	D00419	5			D08511P	B01				YC051-YC052	
0005	24	PK	18-5	23-11-11	D00419	5			D08511P	B01				YC053-YD157	
0006	20	CQ	4-6	33-18-62	D00419	6			TB0804Z	A017	1A			YC051-YD157	
0007	24	PK	17-10	23-11-11	D00419	7			D08511P	A02				YC051-YC052	
0007	24	PK	18-5	23-11-11	D00419	7			D08511P	A02				YC053-YD157	
0008	20	PA	3-11	23-11-11	D00419	8			GD00815	DC..	1A			YC051-YD157	
0009	20	PA	3-11	23-11-11	D00419			FA	GD00815	ST..	1A			YC051-YD157	
0011	20	PA	3-11	23-11-11	D00419	11			GD00815	ST..	1A			YC051-YD157	
0012	20	PA	3-11	23-11-11	D00419	12			GD00815	DC..	1A			YC051-YD157	
0013	22	PA	17-10	23-11-11	D00419	13			D08511P	B05				YC051-YC052	

WIRE LIST

D280A108

91-21-11

Section W2510

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2511	286A2511			HF COMM NO. 1 CONTROL PNL (continued)											
0013	22		PA		18-5	23-11-11	D00419				D08511P	B05			YC053-YD157
0014	22		PA		17-10	23-11-11	D00419				D08511P	A05			YC051-YC052
0014	22		PA		18-5	23-11-11	D00419				D08511P	A05			YC053-YD157
0015	20		PA		3-11	23-11-11	D00419				GD00815	ST..	1A		YC051-YD157
2001B	24		Y2	AA	17-10	23-11-11	D00419				D08511P	B03			YC051-YC052
2001B	24		Y2	AA	18-5	23-11-11	D00419				D08511P	B03			YC053-YD157
2001R	24		Y2	AA	0-0	23-11-11	D00419				D08511P	A03			YC051-YD157
2001Z				AA	0-0	23-11-11	D00419			FA	D08511P	PERG	1F		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W2510

Page 7 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2527	286A2527			CDS - DEU 1 OUTPUT 1 TO COAX SPLITTER 1											
101CO				AA	0-0	31-62-12	D10029		=C1		D40101P		=C1		ALL
101CX			0F	AA	25-11	31-62-12	D10029		=A1		D40101P		=A1		YC051-YC055
101CX			0F	AA	28-8	31-62-12	D10029		=A1		D40101P		=A1		YC056-YD170, YN231
101CX			0F	AA	29-1	31-62-12	D10029		=A1		D40101P		=A1		YL951-YL999, YN232-YR328
W2529	286A2529			CDS - DEU 1 OUTPUT 2 TO COAX SPLITTER 2											
201CO				AA	0-0	31-62-22	D10043		=C1		D40201P		=C1		ALL
201CX			0F	AA	25-9	31-62-22	D10043		=A1		D40201P		=A1		YC051-YC055
201CX			0F	AA	26-11	31-62-22	D10043		=A1		D40201P		=A1		YC056-YD170, YN231
201CX			0F	AA	27-4	31-62-22	D10043		=A1		D40201P		=A1		YL951-YL999, YN232-YR328

WIRE LIST

D280A108

91-21-11

Section W2520

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W2531	286A2531				CDS - DEU 2 OUTPUT 2 TO COAX SPLITTER 3												
301CO				AA	0-0	31-62-12		D10057	= C1			D40301P	= C1			ALL	
301CX		0F		AA	25-11	31-62-12		D10057	= A1			D40301P	= A1			YC051-YC055	
301CX		0F		AA	26-1	31-62-12		D10057	= A1			D40301P	= A1			YC056-YD170, YN231	
301CX		0F		AA	26-6	31-62-12		D10057	= A1			D40301P	= A1			YL951-YL999, YN232-YR328	
W2532	286A2532				J9 BATTERY SHIELD												
0501	*2		CQ		8-9	49-41-11		D00044	+	Q		D11798	+	Q		YC051-YC055	
0501	*2		CQ		8-8	49-41-11		D00044	+	Q		D11798	+	Q		YC056-YD158	
0501	*2		CQ		8-11	49-41-11		D00044	+	Q		D11798	+	Q		YD160-YR328	
0502	*1		CQ		8-8	24-31-11		GD03252	DC..	H8	*	D00044	-	Q	*	YC051-YL959, YN231-YN235	
0502	*1		CQ		8-8	24-31-11		GD03252	DC..	H8		D00044	-	Q		YL963-YL999, YN236-YR328	
0516	*1		CQ		6-3	49-41-11		D11798	-	Q		GD03252	DC..	H8		YC051-YC055	
0516	*1		CQ		6-2	49-41-11		D11798	-	Q		GD03252	DC..	H8		YC056-YD158	
0516	*1		CQ		6-8	49-41-11		D11798	-	Q		GD03252	DC..	H8		YD160-YR328	
0526	02		CQ		4-11	24-31-12		C01209	= L	F		M03055	+	R		ALL	
0527	*1		CQ		0-11	24-31-12		C01209	= B	CK		C01212	A2	CK		YC051-YL959, YN231-YN235	
0527	*1		CQ		1-1	24-31-12		C01209	= B	CK		C01212	A2	CK		YL963-YL999, YN236-YR328	
0528	*1		CQ		4-5	24-31-12		D10328	+	Q		C01212	A2	CK		ALL	
0529	24		B6		1-0	24-31-12		C01209	= B	F		C01210	= B	D		YC051-YL959, YN231-YN235	
0529	24		B6		1-3	24-31-12		C01209	= B	F		C01210	= B	D		YL963-YL999, YN236-YR328	
0530	24		B6		1-9	24-31-12		C01210	= L	D	*	C01212	4	1A		ALL	
0531	*1		CQ		8-8	24-31-12		GD03256	DC..	H8	*	D10328	-	Q	*	YC051-YL959, YN231-YN235	
0531	*1		CQ		8-8	24-31-12		GD03256	DC..	H8		D10328	-	Q		YL963-YL999, YN236-YR328	
0532	02		CQ		2-11	24-31-12		M03055	-	Q		GD03308	DC..	F8		YC051-YD158	
0532	02		CQ		3-0	24-31-12		M03055	-	Q		GD03308	DC..	F8		YD160-YR328	
0533	24		B6		20-5	24-33-11		D48108P	A05			C01210	= L	D	*	YC051-YC055	
0533	24		B6		20-6	24-33-11		D48108P	A05			C01210	= L	D	*	YC056-YD158	
0533	24		B6		20-3	24-33-11		D48108P	A05			C01210	= L	D	*	YD160-YR328	
0534	02		CQ		6-8	24-31-11		M00005	-	Q		GD00752	DC..	F8		YC051-YD158	
0534	02		CQ		6-10	24-31-11		M00005	-	Q		GD00752	DC..	F8		YD160-YR328	

WIRE LIST

D280A108

91-21-11

Section W2530

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description		From				To				Effectivity	
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2532	286A2532			J9 BATTERY SHIELD (continued)											
0537	*1	CQ			6-7	24-31-11	D00044	+	Q		C00142	=B	CK		YC051-YC055
0537	*1	CQ			8-4	24-31-11	D00044	+	Q		C00142	=B	CK		YC056-YD158
0537	*1	CQ			6-9	24-31-11	D00044	+	Q		C00142	=B	CK		YD160-YR328
0538	02	CQ			5-2	24-31-11	C00142	=L	F		M00005	+	R		YC051-YD158
0538	02	CQ			5-7	24-31-11	C00142	=L	F		M00005	+	R		YD160-YR328
2201B	24	PL	KA		26-8	24-31-11	D48108P	A02			GD03252	DC..	H8	*	YC051-YC055
2201B	24	PL	KA		26-10	24-31-11	D48108P	A02			GD03252	DC..	H8	*	YC056-YD158
2201B	24	PL	KA		26-9	24-31-11	D48108P	A02			GD03252	DC..	H8	*	YD160-YD170, YN231
2201B	20	PB	KA		26-9	24-31-11	D48108P	A02			GD03252	DC..	H8	*	YL951-YL959, YN232-YN235
2201B	20	PB	KA		26-9	24-31-11	D48108P	A02			GD03252	DC..	H		YL963-YL999, YN236-YR328
2201R	24	PL	KA		0-0	24-31-11	D48108P	A01			D00044	-	Q	*	YC051-YD170, YN231
2201R	20	PB	KA		0-0	24-31-11	D48108P	A01			D00044	-	Q	*	YL951-YL959, YN232-YN235
2201R	20	PB	KA		0-0	24-31-11	D48108P	A01			D00044	-	G		YL963-YL999, YN236-YR328
2202B	24	PL	KB		27-6	24-31-12	D48108P	A04			GD03256	DC..	H8	*	YC051-YC055, YD160-YD170, YN231
2202B	24	PL	KB		27-8	24-31-12	D48108P	A04			GD03256	DC..	H8	*	YC056-YD158
2202B	20	PB	KB		27-6	24-31-12	D48108P	A04			GD03256	DC..	H8	*	YL951-YL959, YN232-YN235
2202B	20	PB	KB		27-6	24-31-12	D48108P	A04			GD03256	DC..	H		YL963-YL999, YN236-YR328
2202R	24	PL	KB		0-0	24-31-12	D48108P	A03			D10328	-	Q	*	YC051-YD170, YN231
2202R	20	PB	KB		0-0	24-31-12	D48108P	A03			D10328	-	Q	*	YL951-YL959, YN232-YN235
2202R	20	PB	KB		0-0	24-31-12	D48108P	A03			D10328	-	G		YL963-YL999, YN236-YR328
W2533	286A2533			CDS - DEU 2 OUTPUT 1 TO COAX SPLITTER 4											
401CO			AA		0-0	31-62-22	D10071	=C1			D40401P	=C1			ALL
401CX		0F	AA		25-7	31-62-22	D10071	=A1			D40401P	=A1			YC051-YC055
401CX		0F	AA		25-11	31-62-22	D10071	=A1			D40401P	=A1			YC056-YD170, YN231
401CX		0F	AA		26-4	31-62-22	D10071	=A1			D40401P	=A1			YL951-YL999, YN232-YR328
W2534	286A2534			J9 BATTERY SHIELD											
0505	08	CQ			20-11	24-31-12	C01340	=L	70		TB5060I	1	E		ALL

WIRE LIST

D280A108

91-21-11

Section W2530

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2536	286A2536			J9 BATTERY SHIELD											
0506	08		CQ		3-3	24-34-11	M00009	+	G		C01341	A02	F		YC051-YD158
0506	08		CQ		3-5	24-34-11	M00009	+	G		C01341	A02	F		YL951-YL968, YN231-YN236, YN501
0506	08		CQ		3-5	24-34-11	M00009	+	Q		C01341	A02	F		YL969-YL999, YR301-YR328
0513	08		CQ		3-4	24-34-11	M00009	-	F		GD00572	DC..	F		YC051-YD158
0513	08		CQ		3-7	24-34-11	M00009	-	F		GD00572	DC..	F		YL951-YL968, YN231-YN236, YN501
0513	08		CQ		3-7	24-34-11	M00009	-	P		GD00572	DC..	F		YL969-YL999, YR301-YR328
0514	12		CQ		3-9	24-34-11	D00046	3			GD00748	AC..	F		YC051-YC052
0514	12		CQ		3-11	24-34-11	D00046	3			GD00748	AC..	F		YC053-YC055
0514	12		CQ		4-1	24-34-11	D00046	3			GD00748	AC..	F		YC056-YD158
0514	12		CQ		4-0	24-34-11	D00046	3			GD00748	AC..	F		YL951-YN236, YN501-YR328
0515	14		CQ		3-10	24-34-11	D00046	2			GD00270	ST..	E		YC051-YC052
0515	14		CQ		4-0	24-34-11	D00046	2			GD00270	ST..	E		YC053-YC055
0515	14		CQ		4-2	24-34-11	D00046	2			GD00270	ST..	E		YC056-YD158
0515	14		CQ		4-1	24-34-11	D00046	2			GD00270	ST..	E		YL951-YN236, YN501-YR328
0520	12		CQ		33-7	24-34-11	D00046	1			TB5060B	8	E		YC051-YC052
0520	12		CQ		34-0	24-34-11	D00046	1			TB5060B	8	E		YC053-YC055
0520	12		CQ		34-4	24-34-11	D00046	1			TB5060B	8	E		YC056-YD158
0520	12		CQ		34-6	24-34-11	D00046	1			TB5060B	8	E		YL951-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11
Section W2530
Page 3 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To					
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W2589	286A2589				ELT CONTROL PANEL(LEFT SIDE)											
0002	22		PA		6-3	23-24-11	D02889		2			D04889P	6			YC051-YC052
0002	22		PA		6-8	23-24-11	D02889		2			D04889P	6			YC053-YC058
0002	22		PA		6-7	23-24-11	D02889		2			D04889P	6			YC059-YR328
0005	22		PA		6-3	23-24-11	D02889		5			D04889P	3			YC051-YC052
0005	22		PA		6-8	23-24-11	D02889		5			D04889P	3			YC053-YC058
0005	22		PA		6-7	23-24-11	D02889		5			D04889P	3			YC059-YR328
0006	22		PA		4-4	23-24-11	D02889		6			D00483	25			YC051-YC052
0006	22		PA		4-3	23-24-11	D02889		6			D00483	25			YC053-YC058
0006	22		PA		4-5	23-24-11	D02889		6			D00483	25			YC059-YC064
0006	22		PA		4-6	23-24-11	D02889		6			D00483	25			YC065-YR328
0007	22		PA		6-3	23-24-11	D02889		7			D04889P	7			YC051-YC052
0007	22		PA		6-8	23-24-11	D02889		7			D04889P	7			YC053-YC058
0007	22		PA		6-7	23-24-11	D02889		7			D04889P	7			YC059-YR328
0008	22		PA		6-3	23-24-11	D02889		8			D04889P	2			YC051-YC052
0008	22		PA		6-8	23-24-11	D02889		8			D04889P	2			YC053-YC058
0008	22		PA		6-7	23-24-11	D02889		8			D04889P	2			YC059-YR328
0010	22		PA		4-4	23-24-11	D02889		10			D00483	21			YC051-YC052
0010	22		PA		4-3	23-24-11	D02889		10			D00483	21			YC053-YC058
0010	22		PA		4-5	23-24-11	D02889		10			D00483	21			YC059-YC064
0010	22		PA		4-6	23-24-11	D02889		10			D00483	21			YC065-YR328
0011	22		PA		4-4	23-24-11	D02889		11			D00483	1			YC051-YC052
0011	22		PA		4-3	23-24-11	D02889		11			D00483	1			YC053-YC058
0011	22		PA		4-5	23-24-11	D02889		11			D00483	1			YC059-YC064
0011	22		PA		4-6	23-24-11	D02889		11			D00483	1			YC065-YR328
0012	24		PK		3-5	23-24-11	D04889P		9			TB0261X	B013	1A		YC051-YC052
0012	24		PK		3-2	23-24-11	D04889P		9			TB0261X	B013	1A		YC053-YD170
0012	24		PK		3-2	SPARE	D04889P		9			TB0261X	B013	1A		YN231-YN501
0015	22		PA		6-3	23-24-11	D02889		15			D04889P	1			YC051-YC052
0015	22		PA		6-8	23-24-11	D02889		15			D04889P	1			YC053-YC058
0015	22		PA		6-7	23-24-11	D02889		15			D04889P	1			YC059-YR328
0016	22		PA		3-11	23-24-11	TB0503Y	A025	1A			GD00509	DC..	1A		YC051-YC058, YC065-YR328
0016	22		PA		4-1	23-24-11	TB0503Y	A025	1A			GD00509	DC..	1A		YC059-YC064
0017	22		PA		5-1	23-24-11	TB0503Y	A025	1A			D04889P	11			YC051-YC052
0017	22		PA		6-0	23-24-11	TB0503Y	A025	1A			D04889P	11			YC053-YC058
0017	22		PA		5-5	23-24-11	TB0503Y	A025	1A			D04889P	11			YC059-YC064
0017	22		PA		6-1	23-24-11	TB0503Y	A025	1A			D04889P	11			YC065-YR328
2001B	24		Y2	AB	3-5	34-61-15	D04889P		5			TB0261X	B014	1A		YC051-YC052
2001B	24		Y2	AB	3-2	34-61-15	D04889P		5			TB0261X	B014	1A		YC053-YD170

WIRE LIST

D280A108

91-21-11

Section W2580

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2589		286A2589			ELT CONTROL PANEL(LEFT SIDE) (continued)											
2001B		24		Y2	AB	3-2	SPARE	D04889P		5		TB0261X	B014	1A		YN231-YN501
2001R		24		Y2	AB	0-0	34-61-15	D04889P		4		TB0261X	A014	1A		YC051-YD170
2001R		24		Y2	AB	0-0	SPARE	D04889P		4		TB0261X	A014	1A		YN231-YN501
2001Z					AB	0-0	34-61-15	D04889P		8		GB00261	ST..	1A		YC051-YD170
2001Z					AB	0-0	SPARE	D04889P		8		GB00261	ST..	1A		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W2580

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2597	286A2597			E5-2, P61 (DATA LOADER)											
0001	22		PA		13-11	34-21-11	D40625P			1	D45225J	A01			YC051-YC058
0001	22		PA		13-10	34-21-11	D40625P			1	D45225J	A01			YC059-YR328
0002	22		PA		13-11	34-21-11	D40625P			2	D45225J	A02			YC051-YC058
0002	22		PA		13-10	34-21-11	D40625P			2	D45225J	A02			YC059-YR328
0003	22		PA		13-11	34-21-11	D40625P			3	D45225J	A03			YC051-YC058
0003	22		PA		13-10	34-21-11	D40625P			3	D45225J	A03			YC059-YR328
0004	22		PA		13-11	34-21-11	D40625P			4	D45225J	A04			YC051-YC058
0004	22		PA		13-10	34-21-11	D40625P			4	D45225J	A04			YC059-YR328
0005	22		PA		13-11	34-21-16	D40625P			5	D45225J	A05			YC051-YC058
0005	22		PA		13-10	34-21-16	D40625P			5	D45225J	A05			YC059-YR328
0008	24		PK		13-11	31-62-15	D40625P			15	D45225J	A18			YC051-YC058
0008	24		PK		13-10	31-62-15	D40625P			15	D45225J	A18			YC059-YR328
0009	22		PA		13-11	34-61-18	D40625P			13	D45225J	A09			YC051-YC058
0010	22		PA		13-11	34-61-18	D40625P			14	D45225J	A10			YC051-YC058
0011	24		PK		13-11	31-35-01	D40625P			26	D45225J	A13			YC051-YC058
0011	24		PK		13-10	31-35-01	D40625P			26	D45225J	A13			YC059-YR328
0012	24		PK		13-11	31-35-01	D40625P			27	D45225J	A14			YC051-YC058
0012	24		PK		13-10	31-35-01	D40625P			27	D45225J	A14			YC059-YR328
0013	24		PK		13-11	31-35-01	D40625P			28	D45225J	A15			YC051-YC058
0013	24		PK		13-10	31-35-01	D40625P			28	D45225J	A15			YC059-YR328
0014	24		PK		13-11	23-27-11	D40625P			31	D45225J	B17			YC051-YC058
0014	24		PK		13-10	23-27-11	D40625P			31	D45225J	B17			YC059-YD157
0014	24		PK		13-10	23-27-39	D40625P			31	D45225J	B17			YD158-YR328
0016	22		PA		13-11	34-61-18	D45225J			A06	D40625P	8			YC051-YC058
0016	22		PA		13-10	31-32-15	D45225J			A06	D40625P	8			YC059-YR328
0017	22		PA		13-11	23-15-15	D40625P			40	D45225J	B20			YC051-YC058
0017	22		PA		13-10	23-15-15	D40625P			40	D45225J	B20			YC059-YD157
0017	22		PA		13-10	SPARE	D40625P			40	D45225J	B20			YD158-YR328
0018	24		PK		13-11	34-61-18	D40625P			44	D45293J	A03			YC059-YL967, YN231-YN235
0018	24		PK		14-0	34-61-18	D40625P			44	D45293J	A03			YL968-YL999, YN236-YR328
0019	24		PK		13-11	34-61-26	D40625P			41	D45293J	A08			YC059-YL967, YN231-YN235
0019	24		PK		14-0	34-61-26	D40625P			41	D45293J	A08			YL968-YL999, YN236-YR328
0020	24		PK		13-11	22-11-53	D40625P			49	D45293J	A05			YC059-YL967, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W2590

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2597	286A2597				E5-2, P61 (DATA LOADER) (continued)										
0020	24		PK		14-0	22-11-53	D40625P	49			D45293J	A05			YL968-YL999, YN236-YR328
0021	24		PK		13-11	22-11-53	D40625P	50			D45293J	A06			YC059-YL967, YN231-YN235
0021	24		PK		14-0	22-11-53	D40625P	50			D45293J	A06			YL968-YL999, YN236-YR328
0022	24		PK		13-11	22-11-53	D40625P	51			D45293J	A07			YC059-YL967, YN231-YN235
0022	24		PK		14-0	22-11-53	D40625P	51			D45293J	A07			YL968-YL999, YN236-YR328
0023	24		PK		13-11	22-11-53	D40625P	52			D45293J	B03			YC059-YL967, YN231-YN235
0023	24		PK		14-0	22-11-53	D40625P	52			D45293J	B03			YL968-YL999, YN236-YR328
2501B	22		X2	AA	13-11	34-61-18	D40625P	10			D45225J	B02			YC051-YC058
2501B	22		X2	AA	13-10	31-32-15	D40625P	10			D45225J	B02			YC059-YR328
2501R	22		X2	AA	0-0	34-61-18	D40625P	9			D45225J	B01			YC051-YC058
2501R	22		X2	AA	0-0	31-32-15	D40625P	9			D45225J	B01			YC059-YR328
2501Z				AA	0-0	34-61-18	D40625P	S/R			D45225J	PERG	1F		YC051-YC058
2501Z				AA	0-0	31-32-15	D40625P	S/R			D45225J	PERG	1F		YC059-YR328
2502B	22		X2	AB	13-11	34-61-18	D40625P	12			D45225J	B04			YC051-YC058
2502B	22		X2	AB	13-10	SPARE	D40625P	12			D45225J	B04			YC059-YD170, YL955-YL999, YN236-YR328
2502R	22		X2	AB	0-0	34-61-18	D40625P	11			D45225J	B03			YC051-YC058
2502R	22		X2	AB	0-0	SPARE	D40625P	11			D45225J	B03			YC059-YD170, YL955-YL999, YN236-YR328
2502Z				AB	0-0	34-61-18	D40625P	S/R			D45225J	PERG	1F		YC051-YC058
2502Z				AB	0-0	SPARE	D40625P	S/R			D45225J	PERG	1F		YC059-YD170, YL955-YL999, YN236-YR328
2503B	24		Y2	AC	13-11	31-35-01	D40625P	19			D45225J	B06			YC051-YC058
2503B	24		Y2	AC	13-10	31-35-01	D40625P	19			D45225J	B06			YC059-YR328
2503R	24		Y2	AC	0-0	31-35-01	D40625P	18			D45225J	B05			ALL
2503Z				AC	0-0	31-35-01	D40625P	S/R			D45225J	PERG	1F		ALL
2504B	24		Y2	AD	13-11	31-35-01	D40625P	21			D45225J	B08			YC051-YC058
2504B	24		Y2	AD	13-10	31-35-01	D40625P	21			D45225J	B08			YC059-YR328
2504R	24		Y2	AD	0-0	31-35-01	D40625P	20			D45225J	B07			ALL

WIRE LIST

D280A108

91-21-11

Section W2590

Page 2

Nov 12/2012

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From			To						
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W2597	286A2597			E5-2, P61 (DATA LOADER) (continued)											
2504Z				AD	0-0	31-35-01	D40625P	S/R			D45225J	PERG	1F		ALL
2505B	24	Y2	AE		13-11	31-62-15	D40625P	17			D45225J	B10			YC051-YC058
2505B	24	Y2	AE		13-10	31-62-15	D40625P	17			D45225J	B10			YC059-YR328
2505R	24	Y2	AE		0-0	31-62-15	D40625P	16			D45225J	B09			ALL
2505Z			AE		0-0	31-62-15	D40625P	S/R			D45225J	PERG	1F		ALL
2506B	24	Y2	AF		13-11	34-58-11	D40625P	23			D45225J	A12			YC051-YC058
2506B	24	Y2	AF		13-10	34-58-11	D40625P	23			D45225J	A12			YC059-YR328
2506R	24	Y2	AF		0-0	34-58-11	D40625P	22			D45225J	A11			ALL
2506Z			AF		0-0	34-58-11	D40625P	S/R			D45225J	PERG	1F		ALL
2507B	24	Y2	AG		13-11	34-58-11	D40625P	35			D45225J	B12			YC051-YC058
2507B	24	Y2	AG		13-10	34-58-11	D40625P	35			D45225J	B12			YC059-YR328
2507R	24	Y2	AG		0-0	34-58-11	D40625P	34			D45225J	B11			ALL
2507Z			AG		0-0	34-58-11	D40625P	S/R			D45225J	PERG	1F		ALL
2508B	22	X2	AH		13-11	34-61-18	D40625P	30			D45225J	A17			YC051-YC058
2508B	22	X2	AH		13-10	31-32-15	D40625P	30			D45225J	A17			YC059-YR328
2508R	22	X2	AH		0-0	34-61-18	D40625P	29			D45225J	A16			YC051-YC058
2508R	22	X2	AH		0-0	31-32-15	D40625P	29			D45225J	A16			YC059-YR328
2508Z			AH		0-0	34-61-18	D40625P	S/R			D45225J	PERG	1F		YC051-YC058
2508Z			AH		0-0	31-32-15	D40625P	S/R			D45225J	PERG	1F		YC059-YR328
2509B	24	Y2	AI		13-11	23-32-21	D45225J	A20			D40625P	7			YC051-YC058
2509B	24	Y2	AI		13-10	23-32-21	D45225J	A20			D40625P	7			YC059-YD157
2509B	24	Y2	AI		13-10	SPARE	D45225J	A20			D40625P	7			YD158-YR328
2509R	24	Y2	AI		0-0	23-32-21	D45225J	A19			D40625P	6			YC051-YD157
2509R	24	Y2	AI		0-0	SPARE	D45225J	A19			D40625P	6			YD158-YR328
2509Z			AI		0-0	23-32-21	D45225J	PERG	1F		D40625P	S/R			YC051-YD157
2509Z			AI		0-0	SPARE	D45225J	PERG	1F		D40625P	S/R			YD158-YR328
2510B	24	Y2	AJ		13-11	23-27-11	D40625P	25			D45225J	B16			YC051-YC058
2510B	24	Y2	AJ		13-10	23-27-11	D40625P	25			D45225J	B16			YC059-YD157
2510B	24	Y2	AJ		13-10	23-27-39	D40625P	25			D45225J	B16			YD158-YR328
2510R	24	Y2	AJ		0-0	23-27-11	D40625P	24			D45225J	B15			YC051-YD157
2510R	24	Y2	AJ		0-0	23-27-39	D40625P	24			D45225J	B15			YD158-YR328
2510Z			AJ		0-0	23-27-11	D40625P	S/R			D45225J	PERG	1F		YC051-YD157
2510Z			AJ		0-0	23-27-39	D40625P	S/R			D45225J	PERG	1F		YD158-YR328
2512B	22	X2	AL		13-11	49-62-11	D40625P	37			D45225J	B19			YC051-YC058
2512B	22	X2	AL		13-10	49-62-11	D40625P	37			D45225J	B19			YC059-YR328
2512R	22	X2	AL		0-0	49-62-11	D40625P	36			D45225J	B18			ALL
2512Z			AL		0-0	49-62-11	D40625P	S/R			D45225J	PERG	1F		ALL
2513B	22	X2	AM		13-11	23-15-15	D40625P	39			D45225J	B14			YC051-YC058
2513B	22	X2	AM		13-10	23-15-15	D40625P	39			D45225J	B14			YC059-YD157

WIRE LIST

D280A108

91-21-11

Section W2590

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2597	286A2597				E5-2, P61 (DATA LOADER) (continued)										
2513B	22	X2	AM		13-10	SPARE	D40625P		39		D45225J	B14			YD158-YR328
2513R	22	X2	AM		0-0	23-15-15	D40625P		38		D45225J	B13			YC051-YD157
2513R	22	X2	AM		0-0	SPARE	D40625P		38		D45225J	B13			YD158-YR328
2513Z			AM		0-0	23-15-15	D40625P		S/R		D45225J	PERG	1F		YC051-YD157
2513Z			AM		0-0	SPARE	D40625P		S/R		D45225J	PERG	1F		YD158-YR328
2514B	24	Y2	AN		13-11	34-61-18	D40625P		43		D45293J	B01			YC059-YL967, YN231-YN235
2514B	24	Y2	AN		14-0	34-61-18	D40625P		43		D45293J	B01			YL968-YL999, YN236-YR328
2514R	24	Y2	AN		0-0	34-61-18	D40625P		42		D45293J	A01			YC059-YR328
2514Z			AN		0-0	34-61-18	D40625P		S/R		D45293J	PERG	1F		YC059-YR328
2515B	24	Y2	AP		13-11	34-61-18	D40625P		46		D45293J	B02			YC059-YL967, YN231-YN235
2515B	24	Y2	AP		14-0	34-61-18	D40625P		46		D45293J	B02			YL968-YL999, YN236-YR328
2515R	24	Y2	AP		0-0	34-61-18	D40625P		45		D45293J	A02			YC059-YR328
2515Z			AP		0-0	34-61-18	D40625P		S/R		D45293J	PERG	1F		YC059-YR328
2516B	24	Y2	AQ		13-11	34-61-26	D40625P		14		D45293J	A10			YC059-YL967, YN231-YN235
2516B	24	Y2	AQ		14-0	34-61-26	D40625P		14		D45293J	A10			YL968-YL999, YN236-YR328
2516R	24	Y2	AQ		0-0	34-61-26	D40625P		13		D45293J	A09			YC059-YR328
2516Z			AQ		0-0	34-61-26	D40625P		S/R		D45293J	PERG	1F		YC059-YR328
2517B	24	Y2	AR		13-11	22-11-53	D40625P		48		D45293J	B04			YC059-YL967, YN231-YN235
2517B	24	Y2	AR		14-0	22-11-53	D40625P		48		D45293J	B04			YL968-YL999, YN236-YR328
2517R	24	Y2	AR		0-0	22-11-53	D40625P		47		D45293J	A04			YC059-YR328
2517Z			AR		0-0	22-11-53	D40625P		S/R		D45293J	PERG	1F		YC059-YR328
2518B	24	Y2	AS		13-11	23-27-39	D40625P		33		D45293J	B06			YL951-YL954, YN231-YN235
2518R	24	Y2	AS		0-0	23-27-39	D40625P		32		D45293J	B05			YL951-YL954, YN231-YN235
2518Z			AS		0-0	23-27-39	D40625P		S/R		D45293J	PERG	1F		YL951-YL954, YN231-YN235
2519B	24	Y2	AT		13-11	23-27-39	D40625P		54		D45293J	B08			YL951-YL954, YN231-YN235
2519R	24	Y2	AT		0-0	23-27-39	D40625P		53		D45293J	B07			YL951-YL954, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W2590

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2597	286A2597			E5-2, P61 (DATA LOADER) (continued)											
2519Z				AT	0-0	23-27-39	D40625P	S/R			D45293J	PERG	1F		YL951-YL954, YN231-YN235
2520B	24	Y2	AU		13-11	23-27-39	D40625P	12			D45293J	B10			YL951-YL954, YN231-YN235
2520R	24	Y2	AU		0-0	23-27-39	D40625P	11			D45293J	B09			YL951-YL954, YN231-YN235
2520Z				AU	0-0	23-27-39	D40625P	S/R			D45293J	PERG	1F		YL951-YL954, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W2590

Page 5 End

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2651	286A2651			STBY ELEX PWR FROM P18 TO E1 AND P9.											
0001	20		PA		19-2	SPARE	D41807P		1		D41827J	11			ALL
0002	16		PA		9-11	31-62-11	D41807P		2		D41833P	10			ALL
0003	20		PA		19-2	22-14-11	D41807P		3		D41827J	13			ALL
0004	22		PA		19-2	34-51-41	D41807P		15		D41827J	14			ALL
0005	22		PA		19-2	34-51-11	D41807P		5		D41827J	5			ALL
0006	22		PA		19-2	34-51-11	D41807P		19		D41827J	6			ALL
0007	22		PA		19-2	34-31-11	D41807P		7		D41827J	7			ALL
0008	22		CQ		4-10	34-22-11	D41807P		23		SP02185		S		ALL
0009	22		CQ		4-10	34-24-11	D41807P		9		SP02186		S		YC051-YD157
0009	22		CQ		4-10	SPARE	D41807P		9		SP02186		S		YD158-YR328
0010	20		PA		4-10	34-21-11	D41807P		27		SP02085		S		YC051-YD157
0010	20		PA		4-10	SPARE	D41807P		27		SP02085		S		YD158-YR328
0011	20		PA		19-2	34-53-11	D41807P		11		D41827J	4			ALL
0012	20		PA		11-6	SPARE	D41807P		12		D41831P	1			ALL
0013	20		PA		11-6	SPARE	D41807P		13		D41831P	2			ALL
0014	22		PA		11-6	33-27-11	D41807P		14		D41831P	3			ALL
0015	16		PA		11-6	23-12-11	D41807P		4		D41831P	4			YC051-YD157
0015	16		PA		10-2	23-12-11	D41807P		4		SP00165		S		YD158-YR328
0016	20		PA		19-2	34-55-11	D41807P		16		D41827J	8			ALL
0017	22		PA		9-11	31-62-11	D41807P		17		D41833P	1			ALL
0018	20		PA		9-11	SPARE	D41807P		18		D41833P	2			ALL
0019	16		PA		11-6	23-12-11	D41807P		6		D41831P	7			YC051-YD157
0019	16		PA		11-6	SPARE	D41807P		6		D41831P	7			YD158-YR328
0020	20		PA		9-11	SPARE	D41807P		20		D41833P	3			ALL
0021	20		PA		9-11	SPARE	D41807P		21		D41833P	5			ALL
0022	20		PA		9-11	SPARE	D41807P		22		D41833P	6			ALL
0023	16		PA		9-11	31-62-11	D41807P		8		D41833P	7			ALL
0024	20		PA		9-11	22-23-12	D41807P		24		D41833P	8			YC051-YD157, YL951-YL959
0024	20		PA		9-11	MULTI	D41807P		24		D41833P	8			YD158-YD170, YN231-YN235
0024	20		PA		9-11	SPARE	D41807P		24		D41833P	8			YL963-YL999, YN236-YR328
0026	16		PA		13-8	23-12-11	D41831P		4		SP00165		S		YD158-YR328
0027	16		PA		9-11	31-62-11	D41807P		10		D41833P	4			ALL
0029	22		PA		11-6	SPARE	D41807P		29		D41831P	6			YN231-YN501
0031	22		PA		13-11	SPARE	D41831P		9		SP02191		S		YN231-YN501

WIRE LIST

D280A108

91-21-11
Section W2650
Page 1
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To					
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W2653	286A2653			STBY ELEX PWR FROM P18 TO E3.												
0001	20		PA		22-4	SPARE	D41809P		1			D41837P	1			YC051-YC055
0001	20		PA		22-5	SPARE	D41809P		1			D41837P	1			YC056-YR328
0002	22		PA		22-4	SPARE	D41809P		2			D41837P	2			YC051-YC055
0002	22		PA		22-5	SPARE	D41809P		2			D41837P	2			YC056-YR328
0003	22		PA		22-4	34-57-11	D41809P		3			D41837P	3			YC051-YC055
0003	22		PA		22-5	34-57-11	D41809P		3			D41837P	3			YC056-YR328
0004	20		PA		22-4	34-21-11	D41809P		4			D41837P	9			YC051-YC055
0004	20		PA		22-5	34-21-11	D41809P		4			D41837P	9			YC056-YR328
0005	20		PA		22-4	34-21-11	D41809P		5			D41837P	5			YC051-YC055
0005	20		PA		22-5	34-21-11	D41809P		5			D41837P	5			YC056-YR328
0006	20		PA		22-4	34-61-11	D41809P		6			D41837P	6			YC051-YC055
0006	20		PA		22-5	34-61-11	D41809P		6			D41837P	6			YC056-YR328
0007	20		PA		22-4	34-61-11	D41809P		7			D41837P	8			YC051-YC055
0007	20		PA		22-5	34-61-11	D41809P		7			D41837P	8			YC056-YR328
0008	22		PA		22-11	27-32-11	D41809P		8			D41839P	8			ALL
0009	22		PA		22-11	27-32-11	D41809P		9			D41839P	9			ALL
0010	22		PA		22-11	27-32-11	D41809P		10			D41839P	10			ALL
0011	20		PA		22-11	SPARE	D41809P		11			D41839P	1			ALL
0012	20		PA		22-11	SPARE	D41809P		12			D41839P	2			ALL
0013	20		PA		8-7	23-29-11	D41809P		13			TB1808X	A013	1A		YC051-YD157
0014	10		CQ		4-4	30-42-11	D41809P		27	10		SP01080		9		YC062-YR328
0015	16		PA		22-4	31-62-11	D41809P		15			D41837P	4			YC051-YC055
0015	16		PA		22-5	31-62-11	D41809P		15			D41837P	4			YC056-YR328
0019	16		PA		22-4	SPARE	D41809P		19			D41837P	7			YC051-YC055
0019	16		PA		22-5	SPARE	D41809P		19			D41837P	7			YC056-YR328
0023	18		PA		22-4	SPARE	D41809P		23			D41837P	10			YC051-YC055
0023	18		PA		22-5	SPARE	D41809P		23			D41837P	10			YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W2650

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2661	286A2661			STBY ELEX PWR FROM P6 TO E1.											
0001	20	PA		16-3	23-32-12	D46069P		1			D46051P	1			YC051-YD157
0001	20	PA		16-3	23-32-14	D46069P		1			D46051P	1			YD158-YN260
0001	20	PA		16-3	44-21-22	D46069P		1			D46051P	1			YN501-YR328
0002	20	PA		16-3	46-11-11	D46069P		2			D46051P	2			ALL
0003	20	PA		16-3	23-31-01	D46069P		3			D46051P	3			ALL
0004	18	PA		16-3	23-31-01	D46069P		4			D46051P	4			ALL
0005	24	PK		16-3	33-25-11	D46069P		5			D46051P	5			ALL
0006	24	PK		16-3	33-25-11	D46069P		6			D46051P	6			ALL
0007	18	PA		16-3	SPARE	D46069P		7			D46051P	7			ALL
0008	24	B6		16-3	32-41-11	D46069P		8			D46051P	8			ALL
0009	24	PK		16-3	32-42-11	D46069P		9			D46051P	9			ALL
0010	16	PA		16-3	SPARE	D46069P		10			D46051P	10			ALL
0011	24	PK		16-3	32-42-11	D46069P		11			D46051P	11			ALL
0012	24	PK		16-3	32-42-11	D46069P		12			D46051P	12			ALL

WIRE LIST

D280A108

91-21-11

Section W2660

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2702	286A2702			P5 OVHD PANEL TO EE BAY (E2-1) AN2											
0002	20	CQ		29-7	49-62-11	S00248		2NO	B		D40564P	B01			YC051-YC058
0002	20	CQ		29-8	49-62-11	S00248		2NO	B		D40564P	B01			YC059-YR328
0003	20	CQ		29-7	49-62-11	S00248		2NC	B		D40564P	B02			YC051-YC058
0003	20	CQ		29-8	49-62-11	S00248		2NC	B		D40564P	B02			YC059-YR328
0501	22	CQ		29-1	24-22-31	D00634		17			D40564P	A01			YC051-YC064
0501	22	CQ		29-2	24-22-31	D00634		17			D40564P	A01			YC065-YR328
0504	22	CQ		29-1	49-62-11	D00634		6			D40564P	A02			YC051-YC064
0504	22	CQ		29-2	49-62-11	D00634		6			D40564P	A02			YC065-YR328
0505	22	CQ		29-1	49-62-11	D00634		31			D40564P	A03			YC051-YC064
0505	22	CQ		29-2	49-62-11	D00634		31			D40564P	A03			YC065-YR328
0506	22	CQ		29-1	49-62-11	D00634		30			D40564P	A04			YC051-YC064
0506	22	CQ		29-2	49-62-11	D00634		30			D40564P	A04			YC065-YR328
0507	22	CQ		29-1	49-94-21	D00634		19			D40564P	A05			YC051-YC064
0507	22	CQ		29-2	49-94-21	D00634		19			D40564P	A05			YC065-YR328
0508	22	CQ		29-1	49-94-21	D00634		18			D40564P	A06			YC051-YC064
0508	22	CQ		29-2	49-94-21	D00634		18			D40564P	A06			YC065-YR328
2201B	22	X2	KA	28-11	24-22-31	D00722		16			D40564P	A08			YC051-YC058
2201B	22	X2	KA	29-1	24-22-31	D00722		16			D40564P	A08			YC059-YR328
2201R	22	X2	KA	0-0	24-22-31	D00722		15			D40564P	A07			ALL
2201Z			KA	0-0	24-22-31	D00722		DED			D40564P	DED			ALL
2202B	22	X2	KB	29-0	49-71-21	D00446		1			D40564P	A10			ALL
2202R	22	X2	KB	0-0	49-71-21	D00446		2			D40564P	A09			ALL
2202Z			KB	0-0	49-71-21	D00446		DED			D40564P	DED			ALL
3201B	22	X3	YA	29-1	24-22-31	D00634		28			D40564P	B12			YC051-YC064
3201B	22	X3	YA	29-2	24-22-31	D00634		28			D40564P	B12			YC065-YR328
3201R	22	X3	YA	0-0	24-22-31	D00634		29			D40564P	B11			ALL
3201Y	22	X3	YA	0-0	24-22-31	D00634		16			D40564P	B13			ALL
3201Z			YA	0-0	24-22-31	D00634		DED			D40564P	DED			ALL

WIRE LIST

D280A108

91-21-11

Section W2700

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2737	286A2737			P6 TO M2554 SPEEDBRAKE RETRACT ACTUATOR											
0001	20		GA		3-0	27-62-41	D11841			1	GD00053	DC..	E		YC051-YC065
0002	20		GA		3-0	27-62-41	D11841			2	GD00053	DC..	E		YC051-YC065
0003	20		GA		10-0	27-62-41	D40386P			29	D11841		3		YC051-YC065
0004	20		GA		10-0	27-62-41	D40386P			23	D11841		5		YC051-YC065
0005	20		GA		10-0	27-62-41	D40386P			24	D11841		4		YC051-YC065
0006	20		GA		3-0	27-62-41	D11841			6	GD00053	DC..	E		YC051-YC065
0007	20		GA		10-0	27-62-41	D40386P			9	D11841		7		YC051-YC065

WIRE LIST

D280A108

91-21-11

Section W2730

Page 1 End

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2801		286A2801					ACARS CONTROL PANEL									
0001		22		PA		30-6	23-27-13	D43319P	A01			P008-00	CAP	Y		YC051-YC055
0001		22		PA		31-1	23-27-13	D43319P	A01			P008-00	CAP	Y		YC056-YD157
0002		20		PA		3-8	23-27-13	GD00811	AC..	1A		P008-00	CAP	Y		YC051-YD157
0003		20		PA		3-7	23-27-13	GD00801	ST..	1A		P008-00			FA	YC051-YD157
0003		20		PA		3-7	23-27-33	GD00801	ST..	1A		P008-00			FA	YD158-YN260
2501B		24		Y2	AA	30-6	23-27-13	D43319P	B02			P008-00	CAP	Y		YC051-YC055
2501B		24		Y2	AA	31-1	23-27-13	D43319P	B02			P008-00	CAP	Y		YC056-YD157
2501B		24		Y2	AA	31-1	23-27-33	D43319P	B02			P008-00	CAP	Y		YD158-YN260
2501R		24		Y2	AA	0-0	23-27-13	D43319P	A02			P008-00	CAP	Y		YC051-YD157
2501R		24		Y2	AA	0-0	23-27-33	D43319P	A02			P008-00	CAP	Y		YD158-YN260
2501Z					AA	0-0	23-27-13	D43319P	PERG	1F		P008-00			FA	YC051-YD157
2501Z					AA	0-0	23-27-33	D43319P	PERG	1F		P008-00			FA	YD158-YN260
2502B		24		Y2	AB	30-6	23-27-13	D43319P	B03			P008-00	CAP	Y		YC051-YC055
2502B		24		Y2	AB	31-1	23-27-13	D43319P	B03			P008-00	CAP	Y		YC056-YD157
2502B		24		Y2	AB	31-1	23-27-33	D43319P	B03			P008-00	CAP	Y		YD158-YN260
2502R		24		Y2	AB	0-0	23-27-13	D43319P	A03			P008-00	CAP	Y		YC051-YD157
2502R		24		Y2	AB	0-0	23-27-33	D43319P	A03			P008-00	CAP	Y		YD158-YN260
2502Z					AB	0-0	23-27-13	D43319P	PERG	1F		P008-00			FA	YC051-YD157
2502Z					AB	0-0	23-27-33	D43319P	PERG	1F		P008-00			FA	YD158-YN260
2503B		24		Y2	AC	31-1	SPARE	D43319P	B08			P008-00	CAP	Y		YD158-YD170
2503R		24		Y2	AC	0-0	SPARE	D43319P	A08			P008-00	CAP	Y		YD158-YD170
2503Z					AC	0-0	SPARE	D43319P	PERG	1F		P008-00			FA	YD158-YD170
W2803		286A2803					CALSEL ENCODER CONTROL PANEL									
0001		20		PA		10-4	23-29-11	D02525		10		TB1808X	A013	1A		YC051-YD157
0002		20		PA		3-9	23-29-11	D02525		1		GD00803	DC..	1A		YC051-YD157
0003		20		PA		3-9	23-29-11	D02525		2		GD00803	DC..	1A		YC051-YD157
0004		24		PK		4-2	23-29-11	D02525		12		TB0804Z	A009	1A		YC051-YD157
0005		24		PK		4-2	23-29-11	D02525		14		TB0804Z	A009	1A		YC051-YD157
0006		24		PK		4-2	23-29-11	D02525		15		TB0804Z	A009	1A		YC051-YD157
0007		24		PK		4-2	23-29-11	D02525		16		TB0804Z	A009	1A		YC051-YD157
0008		24		PK		4-2	23-29-11	D02525		17		TB0804Z	A009	1A		YC051-YD157
0009		24		PK		4-2	23-29-11	D02525		23		TB0804Z	A009	1A		YC051-YD157
0010		24		PK		4-2	23-29-11	D02525		24		TB0804Z	B009	1A		YC051-YD157
0011		24		PK		4-2	23-29-11	D02525		25		TB0804Z	B009	1A		YC051-YD157
0012		24		PK		4-2	23-29-11	D02525		26		TB0804Z	B009	1A		YC051-YD157
0013		24		PK		4-2	23-29-11	D02525		27		TB0804Z	B009	1A		YC051-YD157
0014		24		PK		4-2	23-29-11	D02525		28		TB0804Z	B009	1A		YC051-YD157
0015		24		PK		4-3	23-29-11	D02525		29		TB0804Y	A007	1A		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W2800

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W2803	286A2803				CALSEL ENCODER CONTROL PANEL (continued)											
0015	24		PK		4-3	23-29-11		D02525		29		TB0804Y	B007	1A		YC053-YD157
0016	24		PK		4-3	23-29-11		D02525		30		TB0804Y	A007	1A		YC051-YC052
0016	24		PK		4-3	23-29-11		D02525		30		TB0804Y	B007	1A		YC053-YD157
0017	24		PK		4-3	23-29-11		D02525		13		TB0804Y	A007	1A		YC051-YC052
0017	24		PK		4-3	23-29-11		D02525		13		TB0804Y	B007	1A		YC053-YD157
0018	24		PK		0-7	23-29-11		TB0804Z	B009	1A		TB0804Z	A009	1A		YC051-YD157
0019	24		PK		1-1	23-29-11		TB0804Z	B009	1A		TB0804Y	A007	1A		YC051-YC052
0019	24		PK		1-1	23-29-11		TB0804Z	B009	1A		TB0804Y	B007	1A		YC053-YD157
0020	20		PA		3-11	23-29-11		D02525			FA	GD00801	ST..	1A		YC051-YD157
0021	22		CQ		27-2	23-29-11		D02525		5		D44145P	A02			YC051-YC055
0021	22		CQ		27-6	23-29-11		D02525		5		D44145P	A02			YC056-YD157
2501B	24		M5	AA	27-2	23-29-11		D02525		9		D44145P	B01			YC051-YC055
2501B	24		M5	AA	27-6	23-29-11		D02525		9		D44145P	B01			YC056-YD157
2501R	24		M5	AA	0-0	23-29-11		D02525		7		D44145P	A01			YC051-YD157
2501ZI				AA	0-0	23-29-11		D02525	DED			D44145P	B02			YC051-YD157
2501ZO				AA	0-0	23-29-11		D02525			FA	D44145P	PERG	1F		YC051-YD157
W2805	286A2805				ACMS PRINTER											
0001	22		PA		28-3	31-33-01		D02649		R		D43215P	A01			YC051-YC055
0001	22		PA		28-8	31-33-01		D02649		R		D43215P	A01			YC056-YR328
0002	20		PA		3-9	31-33-01		D02649		N		GD00803	AC..	1A		ALL
0003	20		PA		3-9	31-33-01		D02649			AA	GD00803	ST..	1A		ALL
0004	20		PA		3-9	31-33-01		D02649		L		GD00803	DC..	1A		ALL
0005	20		PA		4-2	33-11-41		D02649		E-		TB0801W	A017	1		ALL
0006	20		PA		3-9	33-11-41		D02649		M		GD00803	AC..	1A		ALL
2501B	24		Y2	AA	28-3	31-33-01		D02649		F		D43215P	B02			YC051-YC055
2501B	24		Y2	AA	28-8	31-33-01		D02649		F		D43215P	B02			YC056-YR328
2501R	24		Y2	AA	0-0	31-33-01		D02649		E		D43215P	A02			ALL
2501Z				AA	0-0	31-33-01		D02649			AA	D43215P	PERG	1F		ALL
2502B	24		Y2	AB	28-3	31-33-01		D02649		I-		D43215P	B03			YC051-YC055
2502B	24		Y2	AB	28-8	31-33-01		D02649		I-		D43215P	B03			YC056-YR328
2502R	24		Y2	AB	0-0	31-33-01		D02649		H-		D43215P	A03			ALL
2502Z				AB	0-0	31-33-01		D02649			AA	D43215P	PERG	1F		ALL
2503B	24		Y2	AC	28-3	23-27-14		D02649		B		D43215P	B04			YC051-YC055
2503B	24		Y2	AC	28-8	SPARE		D02649		B		D43215P	B04			YC056-YR328
2503R	24		Y2	AC	0-0	23-27-14		D02649		A		D43215P	A04			YC051-YC055
2503R	24		Y2	AC	0-0	SPARE		D02649		A		D43215P	A04			YC056-YR328
2503Z				AC	0-0	23-27-14		D02649			AA	D43215P	PERG	1F		YC051-YC055
2503Z				AC	0-0	SPARE		D02649			AA	D43215P	PERG	1F		YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W2800

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W2805		286A2805			ACMS PRINTER (continued)											
2504B		24		Y2	AD	28-8	23-27-32	D02649		X		D43215P		B05		YD158-YR328
2504R		24		Y2	AD	0-0	23-27-32	D02649		J-		D43215P		A05		YD158-YR328
2504Z					AD	0-0	23-27-32	D02649			AA	D43215P		PERG	1F	YD158-YR328
2505B		24		Y2	AE	28-3	34-61-24	D02649		P-		D43215P		B06		YC051-YC055
2505B		24		Y2	AE	28-8	34-61-24	D02649		P-		D43215P		B06		YC056-YR328
2505R		24		Y2	AE	0-0	34-61-24	D02649		N-		D43215P		A06		ALL
2505Z					AE	0-0	34-61-24	D02649			AA	D43215P		PERG	1F	ALL
2506B		24		Y2	AF	28-3	34-61-24	D02649		T-		D43215P		B07		YC051-YC055
2506B		24		Y2	AF	28-8	34-61-24	D02649		T-		D43215P		B07		YC056-YR328
2506R		24		Y2	AF	0-0	34-61-24	D02649		Q-		D43215P		A07		ALL
2506Z					AF	0-0	34-61-24	D02649			AA	D43215P		PERG	1F	ALL

WIRE LIST

D280A108

91-21-11

Section W2800

Page 3 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From			To						
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W2873	286A2873				FROM FMC TO CONTROL STAND MCDU - NO.2											
0001	20		PA		20-2	34-61-11	D02221		30			D08105J	A01			ALL
0002	22		PA		20-2	34-61-11	D02221		13			D08105J	A02			ALL
0003	20		PA		3-8	34-61-11	D02221		31			GD0911B	AC..	1A		ALL
0004	20		PA		3-8	34-61-11	D02221		12			GD0911B	DC..	1A		ALL
0005	20		PA		3-8	34-61-11	D02221		25			GD0911B	DC..	1A		ALL
0006	20		PA		3-8	34-61-11	D02221		26			GD0911B	DC..	1A		ALL
0008	20		PA		17-2	33-11-41	D02221		28			TB0801W	B005	1		ALL
0009	20		PA		3-8	33-11-41	D02221		29			GD0911B	AC..	1A		ALL
0010	20		CQ		17-4	33-18-61	D02221		27			TB0803Y	A013	1A		ALL
0011	20		CQ		17-6	33-18-61	D02221		23			TB0803Z	B005	1A		ALL
0012	24		PK		20-2	34-61-26	D02221		10			D08105J	A05			YC059-YR328
0013	24		PK		20-2	34-61-26	D02221		7			D08105J	B07			YC059-YR328
2501B	24		Y2	AA	20-2	34-61-11	D02221		9			D08105J	A04			ALL
2501R	24		Y2	AA	0-0	34-61-11	D02221		8			D08105J	A03			ALL
2501Z				AA	0-0	34-61-11	D02221		DED			D08105J	PERG	1F		ALL
2502B	24		Y2	AB	20-2	34-61-11	D02221		3			D08105J	A07			ALL
2502R	24		Y2	AB	0-0	34-61-11	D02221		2			D08105J	A06			ALL
2502Z				AB	0-0	34-61-11	D02221		DED			D08105J	PERG	1F		ALL
2503B	24		Y2	AC	20-2	34-61-23	D02221		17			D08105J	B02			ALL
2503R	24		Y2	AC	0-0	34-61-23	D02221		16			D08105J	B01			ALL
2503Z				AC	0-0	34-61-23	D02221		DED			D08105J	PERG	1F		ALL
2504B	24		Y2	AD	20-2	23-27-13	D02221		15			D08105J	B04			YC051-YD157
2504B	24		Y2	AD	20-2	23-27-33	D02221		15			D08105J	B04			YD158-YR328
2504R	24		Y2	AD	0-0	23-27-13	D02221		14			D08105J	B03			YC051-YD157
2504R	24		Y2	AD	0-0	23-27-33	D02221		14			D08105J	B03			YD158-YR328
2504Z				AD	0-0	23-27-13	D02221		DED			D08105J	PERG	1F		YC051-YD157
2504Z				AD	0-0	23-27-33	D02221		DED			D08105J	PERG	1F		YD158-YR328
2505B	24		Y2	AE	20-2	31-35-02	D02221		19			D08105J	B06			ALL
2505R	24		Y2	AE	0-0	31-35-02	D02221		18			D08105J	B05			ALL
2505Z				AE	0-0	31-35-02	D02221		DED			D08105J	PERG	1F		ALL
2508B	24		Y2	AH	20-2	23-15-15	D02221		24			D08105J	A09			YC051-YD157
2508R	24		Y2	AH	0-0	23-15-15	D02221		20			D08105J	A08			YC051-YD157
2508Z				AH	0-0	23-15-15	D02221		DED			D08105J	PERG	1F		YC051-YD157
2511B	24		Y2	AK	20-2	34-61-26	D02221		6			D08105J	B11			YC059-YR328
2511R	24		Y2	AK	0-0	34-61-26	D02221		5			D08105J	A11			YC059-YR328
2511Z				AK	0-0	34-61-26	D02221		DED			D08105J	PERG	1F		YC059-YR328

WIRE LIST

D280A108

91-21-11

Section W2870

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To							
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice
W2889	286A2889			FROM FMC TO CONTROL STAND CDU - NO.1											
0001	20	PA			28-9	34-61-11	D02181	30			D05925J	A01			YC051-YC058
0001	20	CQ			28-11	34-61-11	D02181	30			D05925J	A01			YC059-YR328
0002	22	PA			28-9	34-61-11	D02181	13			D05925J	A02			YC051-YC058
0002	22	PA			28-11	34-61-11	D02181	13			D05925J	A02			YC059-YR328
0003	20	PA			3-7	34-61-11	D02181	31			GD0901B	AC..	1A		ALL
0004	20	PA			3-7	34-61-11	D02181	11			GD0901B	DC..	1A		ALL
0005	20	PA			3-7	34-61-11	D02181	25			GD0901B	DC..	1A		ALL
0006	20	PA			3-7	34-61-11	D02181	26			GD0901B	DC..	1A		ALL
0008	20	GA			20-6	33-11-41	D02181	28			TB0801W	B005	1		YC051-YC052
0008	20	PA			20-6	33-11-33	D02181	28			TB0801V	A011	1		YC053-YC058
0008	20	PA			20-10	33-11-33	D02181	28			TB0801V	A011	1		YC059-YR328
0009	20	PA			3-7	33-11-33	D02181	29			GD0901B	AC..	1A		ALL
0010	20	CQ			20-9	33-18-61	D02181	27			TB0803Z	A005	1A		YC051-YC058
0010	20	CQ			21-0	33-18-61	D02181	27			TB0803Z	A005	1A		YC059-YR328
0011	20	CQ			20-9	33-18-61	D02181	23			TB0803Z	B005	1A		YC051-YC058
0011	20	CQ			21-0	33-18-61	D02181	23			TB0803Z	B005	1A		YC059-YR328
0012	24	PK			28-11	34-61-26	D02181	10			D05925J	A05			YC059-YR328
0013	24	PK			28-11	34-61-26	D02181	7			D05925J	B07			YC059-YR328
2501B	24	Y2	AA		28-9	34-61-22	D02181	9			D05925J	A04			YC051-YC058
2501B	24	Y2	AA		28-11	34-61-22	D02181	9			D05925J	A04			YC059-YR328
2501R	24	Y2	AA		0-0	34-61-22	D02181	8			D05925J	A03			ALL
2501Z			AA		0-0	34-61-22	D02181	DED			D05925J	PERG	1F		ALL
2502B	24	Y2	AB		28-9	34-61-11	D02181	3			D05925J	A07			YC051-YC058
2502B	24	Y2	AB		28-11	34-61-11	D02181	3			D05925J	A07			YC059-YR328
2502R	24	Y2	AB		0-0	34-61-11	D02181	2			D05925J	A06			ALL
2502Z			AB		0-0	34-61-11	D02181	DED			D05925J	PERG	1F		ALL
2503B	24	Y2	AC		28-9	34-61-23	D02181	17			D05925J	B02			YC051-YC058
2503B	24	Y2	AC		28-11	34-61-23	D02181	17			D05925J	B02			YC059-YR328
2503R	24	Y2	AC		0-0	34-61-23	D02181	16			D05925J	B01			ALL
2503Z			AC		0-0	34-61-23	D02181	DED			D05925J	PERG	1F		ALL
2504B	24	Y2	AD		28-9	23-27-13	D02181	15			D05925J	B04			YC051-YC058
2504B	24	Y2	AD		28-11	23-27-13	D02181	15			D05925J	B04			YC059-YD157
2504B	24	Y2	AD		28-11	23-27-32	D02181	15			D05925J	B04			YD158-YR328
2504R	24	Y2	AD		0-0	23-27-13	D02181	14			D05925J	B03			YC051-YD157
2504R	24	Y2	AD		0-0	23-27-32	D02181	14			D05925J	B03			YD158-YR328
2504Z			AD		0-0	23-27-13	D02181	DED			D05925J	PERG	1F		YC051-YD157
2504Z			AD		0-0	23-27-32	D02181	DED			D05925J	PERG	1F		YD158-YR328
2505B	24	Y2	AE		28-9	31-35-02	D02181	19			D05925J	B06			YC051-YC058
2505B	24	Y2	AE		28-11	31-35-02	D02181	19			D05925J	B06			YC059-YR328

WIRE LIST

D280A108

91-21-11

Section W2880

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
	W2889			286A2889			FROM FMC TO CONTROL STAND CDU - NO.1 (continued)								
	2505R	24	Y2	AE	0-0	31-35-02	D02181	18			D05925J	B05			ALL
	2505Z			AE	0-0	31-35-02	D02181	DED			D05925J	PERG	1F		ALL
	2508B	24	Y2	AH	28-9	23-15-15	D02181	24			D05925J	A09			YC051-YC058
	2508B	24	Y2	AH	28-11	23-15-15	D02181	24			D05925J	A09			YC059-YD157
	2508R	24	Y2	AH	0-0	23-15-15	D02181	20			D05925J	A08			YC051-YD157
	2508Z			AH	0-0	23-15-15	D02181	DED			D05925J	PERG	1F		YC051-YD157
	2511B	24	Y2	AK	28-11	34-61-26	D02181	6			D05925J	B11			YC059-YR328
	2511R	24	Y2	AK	0-0	34-61-26	D02181	5			D05925J	A11			YC059-YR328
	2511Z			AK	0-0	34-61-26	D02181	DED			D05925J	PERG	1F		YC059-YR328

WIRE LIST

D280A108

91-21-11

Section W2880

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	Wire No.	GA	CO TY		Equip	Term		Type	Splice	Equip	Term	Type	Splice			
W3001	286A3001				FWD LT WALL MOUNT LCD MONITOR TO SIDEWALL DISCONNECT											
0001	20		GA		10-11	23-32-33	D10221		1			D10001J	1			YC051-YC062
0001	20		PA		10-4	23-32-33	D10221		1			D10001J	1			YC063-YD155
0002	20		GA		10-11	23-32-33	D10221		2			D10001J	2			YC051-YC062
0002	20		PA		10-4	23-32-33	D10221		2			D10001J	2			YC063-YD155
0003	22		GA		10-11	23-32-33	D10221		10			D10001J	10			YC051-YC062
0003	22		PA		10-4	23-32-33	D10221		10			D10001J	10			YC063-YD155
0004	24		GK		10-11	23-32-33	D10221		6			D10001J	6			YC051-YC062
0004	24		PK		10-4	23-32-33	D10221		6			D10001J	6			YC063-YD155
0005	22		GA		10-11	23-32-33	D10221		9			D10001J	9			YC051-YC062
0005	22		PA		10-4	23-32-33	D10221		9			D10001J	9			YC063-YD155
0007	22		GA		10-11	23-32-33	D10221		4			D10001J	4			YC051-YC062
0007	22		PA		10-4	23-32-33	D10221		4			D10001J	4			YC063-YD155
0008	22		GA		10-11	23-32-33	D10221		7			D10001J	7			YC051-YC062
0008	22		PA		10-4	23-32-33	D10221		7			D10001J	7			YC063-YD155
0009	22		GA		10-11	23-32-33	D10221		8			D10001J	8			YC051-YC062
0009	22		PA		10-4	23-32-33	D10221		8			D10001J	8			YC063-YD155
001CO				AA	0-0	23-32-33	D10221	=C1				D10003J	=C1			YC051-YD155
001CX			OF	AA	10-6	23-32-33	D10221	=A1	5P			D10003J	=A1			YC051-YC062
001CX			OF	AA	9-10	23-32-33	D10221	=A1	5M			D10003J	=A1			YC063-YD155
W3003	286A3003				FWD RT WALL MOUNT LCD MONITOR TO SIDEWALL DISCONNECT											
0001	20		GA		15-6	23-32-33	D10223		1			D10005J	1			YC051-YC062
0001	20		PA		16-7	23-32-33	D10223		1			D10005J	1			YC063-YD157
0002	20		GA		15-6	23-32-33	D10223		2			D10005J	2			YC051-YC062
0002	20		PA		16-7	23-32-33	D10223		2			D10005J	2			YC063-YD157
0003	22		GA		15-6	23-32-33	D10223		10			D10005J	10			YC051-YC062
0003	22		PA		16-7	23-32-33	D10223		10			D10005J	10			YC063-YD157
0004	24		GK		15-6	23-32-33	D10223		6			D10005J	6			YC051-YC062
0004	24		PK		16-7	23-32-33	D10223		6			D10005J	6			YC063-YD157
0005	22		GA		15-6	23-32-33	D10223		9			D10005J	9			YC051-YC062
0005	22		PA		16-7	23-32-33	D10223		9			D10005J	9			YC063-YD157
0007	22		GA		15-6	23-32-33	D10223		4			D10005J	4			YC051-YC062
0007	22		PA		16-7	23-32-33	D10223		4			D10005J	4			YC063-YD157
0008	22		GA		15-6	23-32-33	D10223		7			D10005J	7			YC051-YC062
0008	22		PA		16-7	23-32-33	D10223		7			D10005J	7			YC063-YD157
0009	22		GA		15-6	23-32-33	D10223		8			D10005J	8			YC051-YC062
0009	22		PA		16-7	23-32-33	D10223		8			D10005J	8			YC063-YD157
001CO				AA	0-0	23-32-33	D10223	=C1				D10007J	=C1			YC051-YD157
001CX			OF	AA	15-0	23-32-33	D10223	=A1	5P			D10007J	=A1			YC051-YC062

WIRE LIST

D280A108

91-21-11

Section W3000

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3003	286A3003				FWD RT WALL MOUNT LCD MONITOR TO SIDEWALL DISCONNECT (continued)										
001CX			OF	AA	16-1	23-32-33	D10223	= A1	5M		D10007J	= A1			YC063-YD157
W3004	286A3004				-800 CVR/RIPS										
0001	22		PA		97-0	23-71-01	D40751J	1			D40687P	1			YL963-YL999, YR301-YR328
0001	22		PA		77-9	23-71-01	D40751J	1			D40687P	1			YN236-YN501
0002	14		PA		97-0	23-71-01	D40751J	16			D40687P	10	14		YL963-YL999, YR301-YR328
0002	14		PA		77-9	23-71-01	D40751J	16			D40687P	10	14		YN236-YN501
0004	24		PK		90-1	23-71-01	SP00867		W		D40751J	2			YL963-YL999, YR301-YR328
0004	24		PK		70-10	23-71-01	SP00867		W		D40751J	2			YN236-YN501
W3005	286A3005				PSU MOUNTED LCD VIDEO MONITOR NO. 3 TO VDU IN CLUSTER NO. 1										
0001	20		GA		15-5	23-32-31	D10205	1			D10345	1			YC051-YC062
0001	20		PA		16-4	23-32-31	D10205	1			D10345	1			YC063-YD157
0001	20		PA		16-8	23-32-31	D10205	1			D10333	1			YD158-YD170
0002	20		GA		15-5	23-32-31	D10205	2			D10345	4			YC051-YC062
0002	20		PA		16-4	23-32-31	D10205	2			D10345	4			YC063-YD157
0002	20		PA		16-8	23-32-31	D10205	2			D10333	4			YD158-YD170
0003	22		GA		15-5	23-32-31	D10205	10			D10345	2			YC051-YC062
0003	22		PA		16-4	23-32-31	D10205	10			D10345	2			YC063-YD157
0003	22		PA		16-8	23-32-31	D10205	10			D10333	2			YD158-YD170
0004	24		GK		15-5	23-32-31	D10205	6			D10345	8			YC051-YC062
0004	24		PK		16-4	23-32-31	D10205	6			D10345	8			YC063-YD157
0004	24		PK		16-8	23-32-31	D10205	6			D10333	8			YD158-YD170
0005	22		GA		15-5	23-32-31	D10205	9			D10345	3			YC051-YC062
0005	22		PA		16-4	23-32-31	D10205	9			D10345	3			YC063-YD157
0005	20		PA		16-4	23-32-31	D10205	9			SM00001		S		YD158-YD170
0006	20		PA		0-10	23-32-31	D10333	3			SM00001		S		YD158-YD170
0007	22		GA		15-5	23-32-31	D10345	5			D10205	4			YC051-YC062
0007	22		PA		16-4	23-32-31	D10345	5			D10205	4			YC063-YD157
0007	20		PA		0-10	23-32-31	D10333	5			SM00001		S		YD158-YD170
0008	22		GA		15-5	23-32-31	D10345	6			D10205	7			YC051-YC062
0008	22		PA		16-4	23-32-31	D10345	6			D10205	7			YC063-YD157
0008	20		PA		0-10	23-32-31	D10333	6			SM00001		S		YD158-YD170
0009	22		GA		15-5	23-32-31	D10345	7			D10205	8			YC051-YC062
0009	22		PA		16-4	23-32-31	D10345	7			D10205	8			YC063-YD157
0009	20		PA		0-10	23-32-31	D10333	7			SM00001		S		YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W3000

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3005 286A3005 PSU MOUNTED LCD VIDEO MONITOR NO. 3 TO VDU IN CLUSTER NO. 1 (continued)																
001CO					AA	0-0	23-32-31	D10205	=C1			D10347	=C1			YC051-YD157
001CO					AA	0-0	23-32-31	D10205	=C1			D10335	=C1			YD158-YD170
001CX			OF		AA	14-11	23-32-31	D10205	=A1	5P		D10347	=A1			YC051-YC062
001CX			OF		AA	15-10	23-32-31	D10205	=A1	5M		D10347	=A1			YC063-YD157
001CX			OF		AA	16-2	23-32-31	D10205	=A1	5M		D10335	=A1			YD158-YD170
W3007 286A3007 PSU MOUNTED LCD VIDEO MONITOR NO. 4 TO VDU IN CLUSTER NO. 1																
0001		20		GA		18-7	23-32-31	D10207	1			D10351	1			YC051-YC062
0001		20		PA		19-8	23-32-31	D10207	1			D10351	1			YC063-YD157
0001		20		PA		20-0	23-32-31	D10207	1			D10339	1			YD158-YD170
0002		20		GA		18-7	23-32-31	D10207	2			D10351	4			YC051-YC062
0002		20		PA		19-8	23-32-31	D10207	2			D10351	4			YC063-YD157
0002		20		PA		20-0	23-32-31	D10207	2			D10339	4			YD158-YD170
0003		22		GA		18-7	23-32-31	D10207	10			D10351	2			YC051-YC062
0003		22		PA		19-8	23-32-31	D10207	10			D10351	2			YC063-YD157
0003		22		PA		20-0	23-32-31	D10207	10			D10339	2			YD158-YD170
0004		24		GK		18-7	23-32-31	D10207	6			D10351	8			YC051-YC062
0004		24		PK		19-8	23-32-31	D10207	6			D10351	8			YC063-YD157
0004		24		PK		20-0	23-32-31	D10207	6			D10339	8			YD158-YD170
0005		22		GA		18-7	23-32-31	D10207	9			D10351	3			YC051-YC062
0005		22		PA		19-8	23-32-31	D10207	9			D10351	3			YC063-YD157
0005		20		PA		19-8	23-32-31	D10207	9			SM00001		S		YD158-YD170
0006		20		PA		0-10	23-32-31	D10339	3			SM00001		S		YD158-YD170
0007		22		GA		18-7	23-32-31	D10207	4			D10351	5			YC051-YC062
0007		22		PA		19-8	23-32-31	D10207	4			D10351	5			YC063-YD157
0007		20		PA		0-10	23-32-31	D10339	5			SM00001		S		YD158-YD170
0008		22		GA		18-7	23-32-31	D10207	7			D10351	6			YC051-YC062
0008		22		PA		19-8	23-32-31	D10207	7			D10351	6			YC063-YD157
0008		20		PA		0-10	23-32-31	D10339	6			SM00001		S		YD158-YD170
0009		22		GA		18-7	23-32-31	D10207	8			D10351	7			YC051-YC062
0009		22		PA		19-8	23-32-31	D10207	8			D10351	7			YC063-YD157
0009		20		PA		0-10	23-32-31	D10339	7			SM00001		S		YD158-YD170
001CO					AA	0-0	23-32-31	D10207	=C1			D10351	=C1			YC051-YD157
001CO					AA	0-0	23-32-31	D10207	=C1			D10341	=C1			YD158-YD170
001CX			OF		AA	18-1	23-32-31	D10207	=A1	5P		D10353	=A1			YC051-YC062
001CX			OF		AA	19-2	23-32-31	D10207	=A1	5M		D10353	=A1			YC063-YD157
001CX			OF		AA	19-6	23-32-31	D10207	=A1	5M		D10341	=A1			YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W3000

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I W3009	286A3009			PSU MOUNTED LCD VIDEO MONITOR NO. 5 TO VDU IN CLUSTER NO. 1											
I 0001	20		GA		11-6	23-32-32	D10213				D10357				YC051-YC062
I 0001	20		PA		11-11	23-32-32	D10213				D10357				YC063-YD157
I 0002	20		GA		11-6	23-32-32	D10213				D10357				YC051-YC062
I 0002	20		PA		11-11	23-32-32	D10213				D10357				YC063-YD157
I 0003	22		GA		11-6	23-32-32	D10213				D10357				YC051-YC062
I 0003	22		PA		11-11	23-32-32	D10213				D10357				YC063-YD157
I 0004	24		GK		11-6	23-32-32	D10213				D10357				YC051-YC062
I 0004	24		PK		11-11	23-32-32	D10213				D10357				YC063-YD157
I 0005	22		GA		11-6	23-32-32	D10213				D10357				YC051-YC062
I 0005	22		PA		11-11	23-32-32	D10213				D10357				YC063-YD157
I 0007	22		GA		11-6	23-32-32	D10213				D10357				YC051-YC062
I 0007	22		PA		11-11	23-32-32	D10213				D10357				YC063-YD157
I 0008	22		GA		11-6	23-32-32	D10213				D10357				YC051-YC062
I 0008	22		PA		11-11	23-32-32	D10213				D10357				YC063-YD157
I 0009	22		GA		11-6	23-32-32	D10213				D10357				YC051-YC062
I 0009	22		PA		11-11	23-32-32	D10213				D10357				YC063-YD157
I 001CO				AA	0-0	23-32-32	D10213		= C1		D10359		= C1		YC051-YD157
I 001CX			0F	AA	11-0	23-32-32	D10213		= A1	5P	D10359		= A1		YC051-YC062
I 001CX			0F	AA	11-5	23-32-32	D10213		= A1	5M	D10359		= A1		YC063-YD157

WIRE LIST

D280A108

91-21-11
Section W3000
Page 4 End
Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W3011	286A3011				PSU MOUNTED LCD VIDEO MONITOR NO. 6 TO VDU IN CLUSTER NO. 1											
0001	20		GA		19-1	23-32-32	D10215		1		D10363		1		YC051-YC062	
0001	20		PA		20-1	23-32-32	D10215		1		D10363		1		YC063-YD157	
0002	20		GA		19-1	23-32-32	D10215		2		D10363		4		YC051-YC062	
0002	20		PA		20-1	23-32-32	D10215		2		D10363		4		YC063-YD157	
0003	22		GA		19-1	23-32-32	D10215		10		D10363		2		YC051-YC062	
0003	22		PA		20-1	23-32-32	D10215		10		D10363		2		YC063-YD157	
0004	24		GK		19-1	23-32-32	D10215		6		D10363		8		YC051-YC062	
0004	24		PK		20-1	23-32-32	D10215		6		D10363		8		YC063-YD157	
0005	22		GA		19-1	23-32-32	D10215		9		D10363		3		YC051-YC062	
0005	22		PA		20-1	23-32-32	D10215		9		D10363		3		YC063-YD157	
0007	22		GA		19-1	23-32-32	D10215		4		D10363		5		YC051-YC062	
0007	22		PA		20-1	23-32-32	D10215		4		D10363		5		YC063-YD157	
0008	22		GA		19-1	23-32-32	D10215		7		D10363		6		YC051-YC062	
0008	22		PA		20-1	23-32-32	D10215		7		D10363		6		YC063-YD157	
0009	22		GA		19-1	23-32-32	D10215		8		D10363		7		YC051-YC062	
0009	22		PA		20-1	23-32-32	D10215		8		D10363		7		YC063-YD157	
001CO				AA	0-0	23-32-32	D10215		= C1		D10365		= C1		YC051-YD157	
001CX			OF	AA	18-7	23-32-32	D10215		= A1	5P	D10365		= A1		YC051-YC062	
001CX			OF	AA	19-7	23-32-32	D10215		= A1	5M	D10365		= A1		YC063-YD157	
W3013	286A3013				PSU LCD VIDEO MONITOR (STA 440L TO STA 490L) TO VDU IN CLUSTER 1											
0001	20		PA		14-10	23-32-32	D10213		1		D10357		1		YD158-YD170	
0002	20		PA		14-10	23-32-32	D10213		2		D10357		4		YD158-YD170	
0003	22		PA		14-10	23-32-32	D10213		10		D10357		2		YD158-YD170	
0004	24		PK		14-10	23-32-32	D10213		6		D10357		8		YD158-YD170	
0005	20		PA		14-7	23-32-32	D10213		9		SM00001			S	YD158-YD170	
0006	20		PA		0-9	23-32-32	D10357		3		SM00001			S	YD158-YD170	
0007	20		PA		0-9	23-32-32	D10357		5		SM00001			S	YD158-YD170	
0008	20		PA		0-9	23-32-32	D10357		6		SM00001			S	YD158-YD170	
0009	20		PA		0-9	23-32-32	D10357		7		SM00001			S	YD158-YD170	
001CO				AA	0-0	23-32-32	D10213		= C1		D10359		= C1		YD158-YD170	
001CX			OF	AA	14-4	23-32-32	D10213		= A1	5M	D10359		= A1		YD158-YD170	
W3015	286A3015				PSU LCD VIDEO MONITOR (STA 440R TO 490R) TO VDU IN CLUSTER 1											
0001	20		PA		20-1	23-32-32	D10215		1		D10363		1		YD158-YD170	
0002	20		PA		20-1	23-32-32	D10215		2		D10363		4		YD158-YD170	
0003	22		PA		20-1	23-32-32	D10215		10		D10363		2		YD158-YD170	
0004	24		PK		20-1	23-32-32	D10215		6		D10363		8		YD158-YD170	
0005	20		PA		19-10	23-32-32	D10215		9		SM00001			S	YD158-YD170	

WIRE LIST

D280A108

91-21-11

Section W3010

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3015	286A3015			PSU LCD VIDEO MONITOR (STA 440R TO 490R) TO VDU IN CLUSTER 1 (continued)											
0006	20		PA		0-10	23-32-32	D10363		3		SM00001		S		YD158-YD170
0007	20		PA		0-10	23-32-32	D10363		5		SM00001		S		YD158-YD170
0008	20		PA		0-10	23-32-32	D10363		6		SM00001		S		YD158-YD170
0009	20		PA		0-10	23-32-32	D10363		7		SM00001		S		YD158-YD170
001CO				AA	0-0	23-32-32	D10215		=C1		D10365		=C1		YD158-YD170
001CX		0F		AA	19-7	23-32-32	D10215		=A1	5M	D10365		=A1		YD158-YD170
W3017	286A3017			PSU MOUNTED LCD VIDEO MONITOR NO.9 TO VDU IN CLUSTER NO.2											
0001	20		GA		15-2	23-32-41	D10237		1		D10381		1		YC051-YC062
0001	20		PA		16-2	23-32-41	D10237		1		D10381		1		YC063-YD157
0002	20		GA		15-2	23-32-41	D10237		2		D10381		4		YC051-YC062
0002	20		PA		16-2	23-32-41	D10237		2		D10381		4		YC063-YD157
0003	22		GA		15-2	23-32-41	D10237		10		D10381		2		YC051-YC062
0003	22		PA		16-2	23-32-41	D10237		10		D10381		2		YC063-YD157
0004	24		GK		15-2	23-32-41	D10237		6		D10381		8		YC051-YC062
0004	24		PK		16-2	23-32-41	D10237		6		D10381		8		YC063-YD157
0005	22		GA		15-2	23-32-41	D10237		9		D10381		3		YC051-YC062
0005	22		PA		16-2	23-32-41	D10237		9		D10381		3		YC063-YD157
0007	22		GA		15-2	23-32-41	D10237		4		D10381		5		YC051-YC062
0007	22		PA		16-2	23-32-41	D10237		4		D10381		5		YC063-YD157
0008	22		GA		15-2	23-32-41	D10237		7		D10381		6		YC051-YC062
0008	22		PA		16-2	23-32-41	D10237		7		D10381		6		YC063-YD157
0009	22		GA		15-2	23-32-41	D10237		8		D10381		7		YC051-YC062
0009	22		PA		16-2	23-32-41	D10237		8		D10381		7		YC063-YD157
001CO				AA	0-0	23-32-41	D10237		=C1		D10383		=C1		YC051-YD157
001CX		0F		AA	14-8	23-32-41	D10237		=A1	5P	D10383		=A1		YC051-YC062
001CX		0F		AA	15-8	23-32-41	D10237		=A1	5M	D10383		=A1		YC063-YD157
W3019	286A3019			PSU MOUNTED LCD VIDEO MONITOR NO.10 TO VDU IN CLUSTER NO. 2											
0001	20		GA		19-6	23-32-41	D10239		1		D10387		1		YC051-YC062
0001	20		PA		20-6	23-32-41	D10239		1		D10387		1		YC063-YD157
0002	20		GA		19-6	23-32-41	D10239		2		D10387		4		YC051-YC062
0002	20		PA		20-6	23-32-41	D10239		2		D10387		4		YC063-YD157
0003	22		GA		19-6	23-32-41	D10239		10		D10387		2		YC051-YC062
0003	22		PA		20-6	23-32-41	D10239		10		D10387		2		YC063-YD157
0004	24		GK		19-6	23-32-41	D10239		6		D10387		8		YC051-YC062
0004	24		PK		20-6	23-32-41	D10239		6		D10387		8		YC063-YD157
0005	22		GA		19-6	23-32-41	D10239		9		D10387		3		YC051-YC062
0005	22		PA		20-6	23-32-41	D10239		9		D10387		3		YC063-YD157

WIRE LIST

D280A108

91-21-11

Section W3010

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3019	286A3019			PSU MOUNTED LCD VIDEO MONITOR NO.10 TO VDU IN CLUSTER NO. 2 (continued)											
0007	22		GA		19-6	23-32-41	D10239		4		D10387		5		YC051-YC062
0007	22		PA		20-6	23-32-41	D10239		4		D10387		5		YC063-YD157
0008	22		GA		19-6	23-32-41	D10239		7		D10387		6		YC051-YC062
0008	22		PA		20-6	23-32-41	D10239		7		D10387		6		YC063-YD157
0009	22		GA		19-6	23-32-41	D10239		8		D10387		7		YC051-YC062
0009	22		PA		20-6	23-32-41	D10239		8		D10387		7		YC063-YD157
001CO				AA	0-0	23-32-41	D10239		= C1		D10389		= C1		YC051-YD157
001CX			0F	AA	19-0	23-32-41	D10239		= A1	5P	D10389		= A1		YC051-YC062
001CX			0F	AA	20-1	23-32-41	D10239		= A1	5M	D10389		= A1		YC063-YD157

WIRE LIST

D280A108

91-21-11

Section W3010

Page 3 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

	Bundle No.	Part Number			Fam	Description		From				To				Effectivity
	Wire No.	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
I	W3021	286A3021	PSU MOUNTED LCD VIDEO MONITOR NO.11 TO VDU IN CLUSTER NO.2													
	0001	20		GA		9-3	23-32-42	D10245				D10393	1			YC051-YC062
I	0001	20		PA		10-5	23-32-42	D10245				D10393	1			YC063-YD157
	0001	20		PA		16-8	23-32-41	D10237				D10381	1			YD158-YD170
	0002	20		GA		9-3	23-32-42	D10245				D10393	4			YC051-YC062
I	0002	20		PA		10-5	23-32-42	D10245				D10393	4			YC063-YD157
	0002	20		PA		16-8	23-32-41	D10237				D10381	4			YD158-YD170
	0003	22		GA		9-3	23-32-42	D10245		10		D10393	2			YC051-YC062
I	0003	22		PA		10-5	23-32-42	D10245		10		D10393	2			YC063-YD157
	0003	22		PA		16-8	23-32-41	D10237		10		D10381	2			YD158-YD170
	0004	24		GK		9-3	23-32-42	D10245		6		D10393	8			YC051-YC062
I	0004	24		PK		10-5	23-32-42	D10245		6		D10393	8			YC063-YD157
	0004	24		PK		16-8	23-32-41	D10237		6		D10381	8			YD158-YD170
	0005	22		GA		9-3	23-32-42	D10245		9		D10393	3			YC051-YC062
I	0005	22		PA		10-5	23-32-42	D10245		9		D10393	3			YC063-YD157
	0005	20		PA		16-0	23-32-41	D10237		9		SM00001		S		YD158-YD170
	0006	20		PA		1-2	23-32-41	D10381		3		SM00001		S		YD158-YD170
	0007	22		GA		9-3	23-32-42	D10245		4		D10393	5			YC051-YC062
I	0007	22		PA		10-5	23-32-42	D10245		4		D10393	5			YC063-YD157
	0007	20		PA		1-2	23-32-41	D10381		5		SM00001		S		YD158-YD170
	0008	22		GA		9-3	23-32-42	D10245		7		D10393	6			YC051-YC062
I	0008	22		PA		10-5	23-32-42	D10245		7		D10393	6			YC063-YD157
	0008	20		PA		1-2	23-32-41	D10381		6		SM00001		S		YD158-YD170
	0009	22		GA		9-3	23-32-42	D10245		8		D10393	7			YC051-YC062
I	0009	22		PA		10-5	23-32-42	D10245		8		D10393	7			YC063-YD157
	0009	20		PA		1-2	23-32-41	D10381		7		SM00001		S		YD158-YD170
I	001CO			AA		0-0	23-32-42	D10245	=C1			D10395	=C1			YC051-YD157
	001CO			AA		0-0	23-32-41	D10237	=C1			D10383	=C1			YD158-YD170
	001CX		0F	AA		8-9	23-32-42	D10245	=A1	5P		D10395	=A1			YC051-YC062
I	001CX		0F	AA		10-0	23-32-42	D10245	=A1	5M		D10395	=A1			YC063-YD157
	001CX		0F	AA		16-2	23-32-41	D10237	=A1	5M		D10383	=A1			YD158-YD170
I	W3023	286A3023	PSU MOUNTED LCD VIDEO MONITOR NO.12 TO VDU IN CLUSTER NO.2													
	0001	20		GA		20-0	23-32-42	D10247				D10399	1			YC051-YC062
I	0001	20		PA		20-10	23-32-42	D10247				D10399	1			YC063-YD157
	0001	20		PA		20-5	23-32-41	D10239				D10387	1			YD158-YD170
	0002	20		GA		20-0	23-32-42	D10247				D10399	4			YC051-YC062
I	0002	20		PA		20-10	23-32-42	D10247				D10399	4			YC063-YD157
	0002	20		PA		20-5	23-32-41	D10239				D10387	4			YD158-YD170
	0003	22		GA		20-0	23-32-42	D10247		10		D10399	2			YC051-YC062

WIRE LIST

D280A108

91-21-11

Section W3020

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W3023	286A3023				PSU MOUNTED LCD VIDEO MONITOR NO.12 TO VDU IN CLUSTER NO.2 (continued)											
0003	22		PA		20-10	23-32-42		D10247		10		D10399		2		YC063-YD157
0003	22		PA		20-5	23-32-41		D10239		10		D10387		2		YD158-YD170
0004	24		GK		20-0	23-32-42		D10247		6		D10399		8		YC051-YC062
0004	24		PK		20-10	23-32-42		D10247		6		D10399		8		YC063-YD157
0004	24		PK		20-5	23-32-41		D10239		6		D10387		8		YD158-YD170
0005	22		GA		20-0	23-32-42		D10247		9		D10399		3		YC051-YC062
0005	22		PA		20-10	23-32-42		D10247		9		D10399		3		YC063-YD157
0005	20		PA		19-8	23-32-41		D10239		9		SM00001			S	YD158-YD170
0006	20		PA		1-3	23-32-41		D10387		3		SM00001			S	YD158-YD170
0007	22		GA		20-0	23-32-42		D10247		4		D10399		5		YC051-YC062
0007	22		PA		20-10	23-32-42		D10247		4		D10399		5		YC063-YD157
0007	20		PA		1-3	23-32-41		D10387		5		SM00001			S	YD158-YD170
0008	22		GA		20-0	23-32-42		D10247		7		D10399		6		YC051-YC062
0008	22		PA		20-10	23-32-42		D10247		7		D10399		6		YC063-YD157
0008	20		PA		1-3	23-32-41		D10387		6		SM00001			S	YD158-YD170
0009	22		GA		20-0	23-32-42		D10247		8		D10399		7		YC051-YC062
0009	22		PA		20-10	23-32-42		D10247		8		D10399		7		YC063-YD157
0009	20		PA		1-3	23-32-41		D10387		7		SM00001			S	YD158-YD170
001CO				AA	0-0	23-32-42		D10247	=C1			D10401	=C1			YC051-YD157
001CO				AA	0-0	23-32-41		D10239	=C1			D10389	=C1			YD158-YD170
001CX		0F	AA		19-6	23-32-42		D10247	=A1	5P		D10401	=A1			YC051-YC062
001CX		0F	AA		20-4	23-32-42		D10247	=A1	5M		D10401	=A1			YC063-YD157
001CX		0F	AA		19-11	23-32-41		D10239	=A1	5M		D10389	=A1			YD158-YD170
W3029	286A3029				PSU MOUNTED LCD VIDEO MONITOR NO.15 TO VDU IN CLUSTER NO.2											
0001	20		GA		19-10	23-32-43		D10253		1		D10417		1		YC051-YC062
0001	20		PA		20-2	23-32-43		D10253		1		D10417		1		YC063-YD157
0001	20		PA		8-9	23-32-42		D10245		1		D10405		1		YD158-YD170
0002	20		GA		19-10	23-32-43		D10253		2		D10417		4		YC051-YC062
0002	20		PA		20-2	23-32-43		D10253		2		D10417		4		YC063-YD157
0002	20		PA		8-9	23-32-42		D10245		2		D10405		4		YD158-YD170
0003	22		GA		19-10	23-32-43		D10253		10		D10417		2		YC051-YC062
0003	22		PA		20-2	23-32-43		D10253		10		D10417		2		YC063-YD157
0003	22		PA		8-9	23-32-42		D10245		10		D10405		2		YD158-YD170
0004	24		GK		19-10	23-32-43		D10253		6		D10417		8		YC051-YC062
0004	24		PK		20-2	23-32-43		D10253		6		D10417		8		YC063-YD157
0004	24		PK		8-9	23-32-42		D10245		6		D10405		8		YD158-YD170
0005	22		GA		19-10	23-32-43		D10253		9		D10417		3		YC051-YC062
0005	22		PA		20-2	23-32-43		D10253		9		D10417		3		YC063-YD157

WIRE LIST

D280A108

91-21-11

Section W3020

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3029		286A3029			PSU MOUNTED LCD VIDEO MONITOR NO.15 TO VDU IN CLUSTER NO.2 (continued)											
0005		20		PA		8-5	23-32-42	D10245		9		SM00001		S		YD158-YD170
0006		20		PA		0-10	23-32-42	D10405		3		SM00001		S		YD158-YD170
0007		22		GA		19-10	23-32-43	D10253		4		D10417		5		YC051-YC062
0007		22		PA		20-2	23-32-43	D10253		4		D10417		5		YC063-YD157
0007		20		PA		0-10	23-32-42	D10405		5		SM00001		S		YD158-YD170
0008		22		GA		19-10	23-32-43	D10253		7		D10417		6		YC051-YC062
0008		22		PA		20-2	23-32-43	D10253		7		D10417		6		YC063-YD157
0008		20		PA		0-10	23-32-42	D10405		6		SM00001		S		YD158-YD170
0009		22		GA		19-10	23-32-43	D10253		8		D10417		7		YC051-YC062
0009		22		PA		20-2	23-32-43	D10253		8		D10417		7		YC063-YD157
0009		20		PA		0-10	23-32-42	D10405		7		SM00001		S		YD158-YD170
001CO					AA	0-0	23-32-43	D10253		=C1		D10419		=C1		YC051-YD157
001CO					AA	0-0	23-32-42	D10245		=C1		D10407		=C1		YD158-YD170
001CX			0F		AA	19-4	23-32-43	D10253		=A1	5P	D10419		=A1		YC051-YC062
001CX			0F		AA	19-8	23-32-43	D10253		=A1	5M	D10419		=A1		YC063-YD157
001CX			0F		AA	8-3	23-32-42	D10245		=A1	5M	D10407		=A1		YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W3020

Page 3 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

	Bundle No.	Part Number			Fam	Description		From				To				Effectivity	
		Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
I	W3031	286A3031				PSU MOUNTED LCD VIDEO MONITOR NO.16 TO VDU IN CLUSTER NO.2											
	0001	20		GA		29-11	23-32-43	D10255		1		D10423	1			YC051-YC062	
I	0001	20		PA		30-9	23-32-43	D10255		1		D10423	1			YC063-YD157	
	0001	20		PA		20-10	23-32-42	D10247		1		D10411	1			YD158-YD170	
	0002	20		GA		29-11	23-32-43	D10255		2		D10423	4			YC051-YC062	
I	0002	20		PA		30-9	23-32-43	D10255		2		D10423	4			YC063-YD157	
	0002	20		PA		20-10	23-32-42	D10247		2		D10411	4			YD158-YD170	
	0003	22		GA		29-11	23-32-43	D10255		10		D10423	2			YC051-YC062	
I	0003	22		PA		30-9	23-32-43	D10255		10		D10423	2			YC063-YD157	
	0003	22		PA		20-10	23-32-42	D10247		10		D10411	2			YD158-YD170	
	0004	24		GK		29-11	23-32-43	D10255		6		D10423	8			YC051-YC062	
I	0004	24		PK		30-9	23-32-43	D10255		6		D10423	8			YC063-YD157	
	0004	24		PK		20-10	23-32-42	D10247		6		D10411	8			YD158-YD170	
	0005	22		GA		29-11	23-32-43	D10255		9		D10423	3			YC051-YC062	
I	0005	22		PA		30-9	23-32-43	D10255		9		D10423	3			YC063-YD157	
	0005	20		PA		20-6	23-32-42	D10247		9		SM00001		S		YD158-YD170	
	0006	20		PA		0-10	23-32-42	D10411		3		SM00001		S		YD158-YD170	
	0007	22		GA		29-11	23-32-43	D10255		4		D10423	5			YC051-YC062	
I	0007	22		PA		30-9	23-32-43	D10255		4		D10423	5			YC063-YD157	
	0007	20		PA		0-10	23-32-42	D10411		5		SM00001		S		YD158-YD170	
	0008	22		GA		29-11	23-32-43	D10255		7		D10423	6			YC051-YC062	
I	0008	22		PA		30-9	23-32-43	D10255		7		D10423	6			YC063-YD157	
	0008	20		PA		0-10	23-32-42	D10411		6		SM00001		S		YD158-YD170	
	0009	22		GA		29-11	23-32-43	D10255		8		D10423	7			YC051-YC062	
I	0009	22		PA		30-9	23-32-43	D10255		8		D10423	7			YC063-YD157	
	0009	20		PA		0-10	23-32-42	D10411		7		SM00001		S		YD158-YD170	
I	001CO			AA		0-0	23-32-43	D10255		=C1		D10425		=C1		YC051-YD157	
	001CO			AA		0-0	23-32-42	D10247		=C1		D10413		=C1		YD158-YD170	
	001CX			0F	AA	29-5	23-32-43	D10255		=A1	5P	D10425		=A1		YC051-YC062	
I	001CX			0F	AA	30-3	23-32-43	D10255		=A1	5M	D10425		=A1		YC063-YD157	
	001CX			0F	AA	20-4	23-32-42	D10247		=A1	5M	D10413		=A1		YD158-YD170	
I	W3033	286A3033				PSU MOUNTED LCD VIDEO MONITOR NO.17 TO VDU IN CLUSTER NO.3											
	0001	20		GA		14-8	23-32-51	D10269		1		D10429	1			YC051-YC062	
I	0001	20		PA		15-11	23-32-51	D10269		1		D10429	1			YC063-YD157	
	0002	20		GA		14-8	23-32-51	D10269		2		D10429	4			YC051-YC062	
I	0002	20		PA		15-11	23-32-51	D10269		2		D10429	4			YC063-YD157	
	0003	22		GA		14-8	23-32-51	D10269		10		D10429	2			YC051-YC062	
I	0003	22		PA		15-11	23-32-51	D10269		10		D10429	2			YC063-YD157	
	0004	24		GK		14-8	23-32-51	D10269		6		D10429	8			YC051-YC062	

WIRE LIST

D280A108

91-21-11

Section W3030

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W3033	286A3033				PSU MOUNTED LCD VIDEO MONITOR NO.17 TO VDU IN CLUSTER NO.3 (continued)											
0004	24		PK		15-11	23-32-51		D10269		6		D10429		8		YC063-YD157
0005	22		GA		14-8	23-32-51		D10269		9		D10429		3		YC051-YC062
0005	22		PA		15-11	23-32-51		D10269		9		D10429		3		YC063-YD157
0007	22		GA		14-8	23-32-51		D10269		4		D10429		5		YC051-YC062
0007	22		PA		15-11	23-32-51		D10269		4		D10429		5		YC063-YD157
0008	22		GA		14-8	23-32-51		D10269		7		D10429		6		YC051-YC062
0008	22		PA		15-11	23-32-51		D10269		7		D10429		6		YC063-YD157
0009	22		GA		14-8	23-32-51		D10269		8		D10429		7		YC051-YC062
0009	22		PA		15-11	23-32-51		D10269		8		D10429		7		YC063-YD157
001CO				AA	0-0	23-32-51		D10269		=C1		D10431		=C1		YC051-YD157
001CX			OF	AA	14-2	23-32-51		D10269		=A1	5P	D10431		=A1		YC051-YC062
001CX			OF	AA	15-5	23-32-51		D10269		=A1	5M	D10431		=A1		YC063-YD157
W3035	286A3035				PSU MOUNTED LCD VIDEO MONITOR NO.18 TO VDU IN CLUSTER NO.3											
0001	20		GA		20-11	23-32-51		D10271		1		D10435		1		YC051-YC062
0001	20		PA		23-1	23-32-51		D10271		1		D10435		1		YC063-YD157
0002	20		GA		20-11	23-32-51		D10271		2		D10435		4		YC051-YC062
0002	20		PA		23-1	23-32-51		D10271		2		D10435		4		YC063-YD157
0003	22		GA		20-11	23-32-51		D10271		10		D10435		2		YC051-YC062
0003	22		PA		23-1	23-32-51		D10271		10		D10435		2		YC063-YD157
0004	24		GK		20-11	23-32-51		D10271		6		D10435		8		YC051-YC062
0004	24		PK		23-1	23-32-51		D10271		6		D10435		8		YC063-YD157
0005	22		GA		20-11	23-32-51		D10271		9		D10435		3		YC051-YC062
0005	22		PA		23-1	23-32-51		D10271		9		D10435		3		YC063-YD157
0007	22		GA		20-11	23-32-51		D10271		4		D10435		5		YC051-YC062
0007	22		PA		23-1	23-32-51		D10271		4		D10435		5		YC063-YD157
0008	22		GA		20-11	23-32-51		D10271		7		D10435		6		YC051-YC062
0008	22		PA		23-1	23-32-51		D10271		7		D10435		6		YC063-YD157
0009	22		GA		20-11	23-32-51		D10271		8		D10435		7		YC051-YC062
0009	22		PA		23-1	23-32-51		D10271		8		D10435		7		YC063-YD157
001CO				AA	0-0	23-32-51		D10271		=C1		D10437		=C1		YC051-YD157
001CX			OF	AA	20-5	23-32-51		D10271		=A1	5P	D10437		=A1		YC051-YC062
001CX			OF	AA	22-7	23-32-51		D10271		=A1	5M	D10437		=A1		YC063-YD157
W3037	286A3037				PSU LCD VIDEO MONITOR (STA 530L TO STA 578L)TO VDU IN TRAY 2											
0001	20		PA		20-7	23-32-43		D10253		1		D10429		1		YD158-YD170
0002	20		PA		20-7	23-32-43		D10253		2		D10429		4		YD158-YD170
0003	22		PA		20-7	23-32-43		D10253		10		D10429		2		YD158-YD170
0004	24		PK		20-7	23-32-43		D10253		6		D10429		8		YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W3030

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3037	286A3037			PSU LCD VIDEO MONITOR (STA 530L TO STA 578L) TO VDU IN TRAY 2 (continued)											
0005	20		PA		20-3	23-32-43	D10253		9		SM00001		S		YD158-YD170
0006	20		PA		0-11	23-32-43	D10429		3		SM00001		S		YD158-YD170
0007	20		PA		0-11	23-32-43	D10429		5		SM00001		S		YD158-YD170
0008	20		PA		0-11	23-32-43	D10429		6		SM00001		S		YD158-YD170
0009	20		PA		0-11	23-32-43	D10429		7		SM00001		S		YD158-YD170
001CO				AA	0-0	23-32-43	D10253		= C1		D10431		= C1		YD158-YD170
001CX				0F AA	20-1	23-32-43	D10253		= A1	5M	D10431		= A1		YD158-YD170
W3039	286A3039			PSU LCD VIDEO MONITOR (STA 530R TO STA 578R) TO VDU IN TRAY 2											
0001	20		PA		30-8	23-32-43	D10255		1		D10435		1		YD158-YD170
0002	20		PA		30-8	23-32-43	D10255		2		D10435		4		YD158-YD170
0003	22		PA		30-8	23-32-43	D10255		10		D10435		2		YD158-YD170
0004	24		PK		30-8	23-32-43	D10255		6		D10435		8		YD158-YD170
0005	20		PA		30-4	23-32-43	D10255		9		SM00001		S		YD158-YD170
0006	20		PA		0-10	23-32-43	D10435		3		SM00001		S		YD158-YD170
0007	20		PA		0-10	23-32-43	D10435		5		SM00001		S		YD158-YD170
0008	20		PA		0-10	23-32-43	D10435		6		SM00001		S		YD158-YD170
0009	20		PA		0-10	23-32-43	D10435		7		SM00001		S		YD158-YD170
001CO				AA	0-0	23-32-43	D10255		= C1		D10437		= C1		YD158-YD170
001CX				0F AA	30-2	23-32-43	D10255		= A1	5M	D10437		= A1		YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W3030

Page 3 End

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I W3041	286A3041			PSU MOUNTED LCD VIDEO MONITOR NO.21 TO VDU IN CLUSTER NO.3											
0001	20		GA		13-10	23-32-52	D10277		1		D10453		1		YC051-YC062
I 0001	20		PA		14-11	23-32-52	D10277		1		D10453		1		YC063-YD157
0002	20		GA		13-10	23-32-52	D10277		2		D10453		4		YC051-YC062
I 0002	20		PA		14-11	23-32-52	D10277		2		D10453		4		YC063-YD157
0003	22		GA		13-10	23-32-52	D10277		10		D10453		2		YC051-YC062
I 0003	22		PA		14-11	23-32-52	D10277		10		D10453		2		YC063-YD157
0004	24		GK		13-10	23-32-52	D10277		6		D10453		8		YC051-YC062
I 0004	24		PK		14-11	23-32-52	D10277		6		D10453		8		YC063-YD157
0005	22		GA		13-10	23-32-52	D10277		9		D10453		3		YC051-YC062
I 0005	22		PA		14-11	23-32-52	D10277		9		D10453		3		YC063-YD157
0007	22		GA		13-10	23-32-52	D10277		4		D10453		5		YC051-YC062
I 0007	22		PA		14-11	23-32-52	D10277		4		D10453		5		YC063-YD157
0008	22		GA		13-10	23-32-52	D10277		7		D10453		6		YC051-YC062
I 0008	22		PA		14-11	23-32-52	D10277		7		D10453		6		YC063-YD157
0009	22		GA		13-10	23-32-52	D10277		8		D10453		7		YC051-YC062
I 0009	22		PA		14-11	23-32-52	D10277		8		D10453		7		YC063-YD157
I 001CO				AA	0-0	23-32-52	D10277		= C1		D10455		= C1		YC051-YD157
001CX			OF	AA	13-4	23-32-52	D10277		= A1	5P	D10455		= A1		YC051-YC062
I 001CX			OF	AA	14-5	23-32-52	D10277		= A1	5M	D10455		= A1		YC063-YD157
I W3043	286A3043			PSU LCD VIDEO MONITOR TO VDU IN CLUSTER 3.											
0001	20		GA		19-9	23-32-52	D10279		1		D10459		1		YC051-YC062
I 0001	20		PA		20-6	23-32-52	D10279		1		D10459		1		YC063-YD157
0002	20		GA		19-9	23-32-52	D10279		2		D10459		4		YC051-YC062
I 0002	20		PA		20-6	23-32-52	D10279		2		D10459		4		YC063-YD157
0003	22		GA		19-9	23-32-52	D10279		10		D10459		2		YC051-YC062
I 0003	22		PA		20-6	23-32-52	D10279		10		D10459		2		YC063-YD157
0004	24		GK		19-9	23-32-52	D10279		6		D10459		8		YC051-YC062
I 0004	24		PK		20-6	23-32-52	D10279		6		D10459		8		YC063-YD157
0005	22		GA		19-9	23-32-52	D10279		9		D10459		3		YC051-YC062
I 0005	22		PA		20-6	23-32-52	D10279		9		D10459		3		YC063-YD157
0007	22		GA		19-9	23-32-52	D10279		4		D10459		5		YC051-YC062
I 0007	22		PA		20-6	23-32-52	D10279		4		D10459		5		YC063-YD157
0008	22		GA		19-9	23-32-52	D10279		7		D10459		6		YC051-YC062
I 0008	22		PA		20-6	23-32-52	D10279		7		D10459		6		YC063-YD157
0009	22		GA		19-9	23-32-52	D10279		8		D10459		7		YC051-YC062
I 0009	22		PA		20-6	23-32-52	D10279		8		D10459		7		YC063-YD157
I 001CO				AA	0-0	23-32-52	D10279		= C1		D10461		= C1		YC051-YD157
001CX			OF	AA	19-2	23-32-52	D10279		= A1	5P	D10461		= A1		YC051-YC062

WIRE LIST

D280A108

91-21-11

Section W3040

Page 1

Nov 12/2012

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W3043	286A3043			PSU LCD VIDEO MONITOR TO VDU IN CLUSTER 3. (continued)										
001CX		OF	AA	20-0	23-32-52	D10279	=A1	5M		D10461	=A1			YC063-YD157
W3045	286A3045			PSU MOUNTED LCD VIDEO MONITOR NO.23 TO VDU IN CLUSTER NO.3										
0001	20	GA		22-11	23-32-53	D10285		1		D10465		1		YC051-YC062
0001	20	PA		23-3	23-32-53	D10285		1		D10465		1		YC063-YD157
0001	20	PA		16-8	23-32-51	D10269		1		D10453		1		YD158-YD170
0002	20	GA		22-11	23-32-53	D10285		2		D10465		4		YC051-YC062
0002	20	PA		23-3	23-32-53	D10285		2		D10465		4		YC063-YD157
0002	20	PA		16-8	23-32-51	D10269		2		D10453		4		YD158-YD170
0003	22	GA		22-11	23-32-53	D10285		10		D10465		2		YC051-YC062
0003	22	PA		23-3	23-32-53	D10285		10		D10465		2		YC063-YD157
0003	22	PA		16-8	23-32-51	D10269		10		D10453		2		YD158-YD170
0004	24	GK		22-11	23-32-53	D10285		6		D10465		8		YC051-YC062
0004	24	PK		23-3	23-32-53	D10285		6		D10465		8		YC063-YD157
0004	24	PK		16-8	23-32-51	D10269		6		D10453		8		YD158-YD170
0005	22	GA		22-11	23-32-53	D10285		9		D10465		3		YC051-YC062
0005	22	PA		23-3	23-32-53	D10285		9		D10465		3		YC063-YD157
0005	20	PA		16-4	23-32-51	D10269		9		SM00001			S	YD158-YD170
0006	20	PA		0-10	23-32-51	D10453		3		SM00001			S	YD158-YD170
0007	22	GA		22-11	23-32-53	D10285		4		D10465		5		YC051-YC062
0007	22	PA		23-3	23-32-53	D10285		4		D10465		5		YC063-YD157
0007	20	PA		0-10	23-32-51	D10453		5		SM00001			S	YD158-YD170
0008	22	GA		22-11	23-32-53	D10285		7		D10465		6		YC051-YC062
0008	22	PA		23-3	23-32-53	D10285		7		D10465		6		YC063-YD157
0008	20	PA		0-10	23-32-51	D10453		6		SM00001			S	YD158-YD170
0009	22	GA		22-11	23-32-53	D10285		8		D10465		7		YC051-YC062
0009	22	PA		23-3	23-32-53	D10285		8		D10465		7		YC063-YD157
0009	20	PA		0-10	23-32-51	D10453		7		SM00001			S	YD158-YD170
001CO			AA	0-0	23-32-53	D10285	=C1			D10467	=C1			YC051-YD157
001CO			AA	0-0	23-32-51	D10269	=C1			D10455	=C1			YD158-YD170
001CX		OF	AA	22-5	23-32-53	D10285	=A1	5P		D10467	=A1			YC051-YC062
001CX		OF	AA	22-9	23-32-53	D10285	=A1	5M		D10467	=A1			YC063-YD157
001CX		OF	AA	16-2	23-32-51	D10269	=A1	5M		D10455	=A1			YD158-YD170
W3047	286A3047			PSU MOUNTED LCD VIDEO MONITOR NO.24 TO VDU IN CLUSTER NO.3										
0001	20	GA		26-11	23-32-53	D10287		1		D10471		1		YC051-YC062
0001	20	PA		29-1	23-32-53	D10287		1		D10471		1		YC063-YD157
0001	20	PA		23-11	23-32-51	D10271		1		D10459		1		YD158-YD170
0002	20	GA		26-11	23-32-53	D10287		2		D10471		4		YC051-YC062

WIRE LIST

D280A108

91-21-11

Section W3040

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3047	286A3047			PSU MOUNTED LCD VIDEO MONITOR NO.24 TO VDU IN CLUSTER NO.3 (continued)											
0002	20		PA		29-1	23-32-53	D10287		2		D10471		4		YC063-YD157
0002	20		PA		23-11	23-32-51	D10271		2		D10459		4		YD158-YD170
0003	22		GA		26-11	23-32-53	D10287		10		D10471		2		YC051-YC062
0003	22		PA		29-1	23-32-53	D10287		10		D10471		2		YC063-YD157
0003	22		PA		23-11	23-32-51	D10271		10		D10459		2		YD158-YD170
0004	24		GK		26-11	23-32-53	D10287		6		D10471		8		YC051-YC062
0004	24		PK		29-1	23-32-53	D10287		6		D10471		8		YC063-YD157
0004	24		PK		23-11	23-32-51	D10271		6		D10459		8		YD158-YD170
0005	22		GA		26-11	23-32-53	D10287		9		D10471		3		YC051-YC062
0005	22		PA		29-1	23-32-53	D10287		9		D10471		3		YC063-YD157
0005	20		PA		23-7	23-32-51	D10271		9		SM00001			S	YD158-YD170
0006	20		PA		0-11	23-32-51	D10459		3		SM00001			S	YD158-YD170
0007	22		GA		26-11	23-32-53	D10287		4		D10471		5		YC051-YC062
0007	22		PA		29-1	23-32-53	D10287		4		D10471		5		YC063-YD157
0007	20		PA		0-11	23-32-51	D10459		5		SM00001			S	YD158-YD170
0008	22		GA		26-11	23-32-53	D10287		7		D10471		6		YC051-YC062
0008	22		PA		29-1	23-32-53	D10287		7		D10471		6		YC063-YD157
0008	20		PA		0-11	23-32-51	D10459		6		SM00001			S	YD158-YD170
0009	22		GA		26-11	23-32-53	D10287		8		D10471		7		YC051-YC062
0009	22		PA		29-1	23-32-53	D10287		8		D10471		7		YC063-YD157
0009	20		PA		0-11	23-32-51	D10459		7		SM00001			S	YD158-YD170
001CO				AA	0-0	23-32-53	D10287		=C1		D10473		=C1		YC051-YD157
001CO				AA	0-0	23-32-51	D10271		=C1		D11005		=C1		YD158-YD170
001CX		0F		AA	26-5	23-32-53	D10287		=A1	5P	D10473		=A1		YC051-YC062
001CX		0F		AA	28-6	23-32-53	D10287		=A1	5M	D10473		=A1		YC063-YD157
001CX		0F		AA	23-5	23-32-51	D10271		=A1	5M	D11005		=A1		YD158-YD170

WIRE LIST

D280A108

91-21-11
Section W3040
Page 3 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I W3053	286A3053	PSU MOUNTED LCD VIDEO MONITOR NO.27 TO VDU IN CLUSTER NO.4													
	0001	20	GA		11-4	23-32-61	D10301		1		D10489		1		YC051-YC062
I	0001	20	PA		12-5	23-32-61	D10301		1		D10489		1		YC063-YD157
	0001	20	PA		16-0	23-32-52	D10277		1		D10477		1		YD158-YD170
	0002	20	GA		11-4	23-32-61	D10301		2		D10489		4		YC051-YC062
I	0002	20	PA		12-5	23-32-61	D10301		2		D10489		4		YC063-YD157
	0002	20	PA		16-0	23-32-52	D10277		2		D10477		4		YD158-YD170
	0003	22	GA		11-4	23-32-61	D10301		10		D10489		2		YC051-YC062
I	0003	22	PA		12-5	23-32-61	D10301		10		D10489		2		YC063-YD157
	0003	22	PA		16-0	23-32-52	D10277		10		D10477		2		YD158-YD170
	0004	24	GK		11-4	23-32-61	D10301		6		D10489		8		YC051-YC062
I	0004	24	PK		12-5	23-32-61	D10301		6		D10489		8		YC063-YD157
	0004	24	PK		16-0	23-32-52	D10277		6		D10477		8		YD158-YD170
	0005	22	GA		11-4	23-32-61	D10301		9		D10489		3		YC051-YC062
I	0005	22	PA		12-5	23-32-61	D10301		9		D10489		3		YC063-YD157
	0005	20	PA		15-2	23-32-52	D10277		9		SM00001			S	YD158-YD170
	0006	20	PA		1-4	23-32-52	D10477		3		SM00001			S	YD158-YD170
	0007	22	GA		11-4	23-32-61	D10301		4		D10489		5		YC051-YC062
I	0007	22	PA		12-5	23-32-61	D10301		4		D10489		5		YC063-YD157
	0007	20	PA		1-4	23-32-52	D10477		5		SM00001			S	YD158-YD170
	0008	22	GA		11-4	23-32-61	D10301		7		D10489		6		YC051-YC062
I	0008	22	PA		12-5	23-32-61	D10301		7		D10489		6		YC063-YD157
	0008	20	PA		1-4	23-32-52	D10477		6		SM00001			S	YD158-YD170
	0009	22	GA		11-4	23-32-61	D10301		8		D10489		7		YC051-YC062
I	0009	22	PA		12-5	23-32-61	D10301		8		D10489		7		YC063-YD157
	0009	20	PA		1-4	23-32-52	D10477		7		SM00001			S	YD158-YD170
I	001CO			AA	0-0	23-32-61	D10301		=C1		D10491		=C1		YC051-YD157
	001CO			AA	0-0	23-32-52	D10277		=C1		D10479		=C1		YD158-YD170
	001CX		0F	AA	10-9	23-32-61	D10301		=A1	5P	D10491		=A1		YC051-YC062
I	001CX		0F	AA	11-11	23-32-61	D10301		=A1	5M	D10491		=A1		YC063-YD157
	001CX		0F	AA	15-6	23-32-52	D10277		=A1	5M	D10479		=A1		YD158-YD170
I W3055	286A3055	PSU MOUNTED LCD VIDEO MONITOR NO.28 TO VDU IN CLUSTER NO.4													
	0001	20	GA		16-4	23-32-61	D10303		1		D10495		1		YC051-YC062
I	0001	20	PA		18-5	23-32-61	D10303		1		D10495		1		YC063-YD157
	0001	20	PA		21-7	23-32-52	D10279		1		D10483		1		YD158-YD170
	0002	20	GA		16-4	23-32-61	D10303		2		D10495		4		YC051-YC062
I	0002	20	PA		18-5	23-32-61	D10303		2		D10495		4		YC063-YD157
	0002	20	PA		21-7	23-32-52	D10279		2		D10483		4		YD158-YD170
	0003	22	GA		16-4	23-32-61	D10303		10		D10495		2		YC051-YC062

WIRE LIST

D280A108

91-21-11

Section W3050

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W3055	286A3055				PSU MOUNTED LCD VIDEO MONITOR NO.28 TO VDU IN CLUSTER NO.4 (continued)											
0003	22		PA		18-5	23-32-61		D10303		10		D10495		2		YC063-YD157
0003	22		PA		21-7	23-32-52		D10279		10		D10483		2		YD158-YD170
0004	24		GK		16-4	23-32-61		D10303		6		D10495		8		YC051-YC062
0004	24		PK		18-5	23-32-61		D10303		6		D10495		8		YC063-YD157
0004	24		PK		21-7	23-32-52		D10279		6		D10483		8		YD158-YD170
0005	22		GA		16-4	23-32-61		D10303		9		D10495		3		YC051-YC062
0005	22		PA		18-5	23-32-61		D10303		9		D10495		3		YC063-YD157
0005	20		PA		21-3	23-32-52		D10279		9		SM00001			S	YD158-YD170
0006	20		PA		0-11	23-32-52		D10483		3		SM00001			S	YD158-YD170
0007	22		GA		16-4	23-32-61		D10303		4		D10495		5		YC051-YC062
0007	22		PA		18-5	23-32-61		D10303		4		D10495		5		YC063-YD157
0007	20		PA		0-11	23-32-52		D10483		5		SM00001			S	YD158-YD170
0008	22		GA		16-4	23-32-61		D10303		7		D10495		6		YC051-YC062
0008	22		PA		18-5	23-32-61		D10303		7		D10495		6		YC063-YD157
0008	20		PA		0-11	23-32-52		D10483		6		SM00001			S	YD158-YD170
0009	22		GA		16-4	23-32-61		D10303		8		D10495		7		YC051-YC062
0009	22		PA		18-5	23-32-61		D10303		8		D10495		7		YC063-YD157
0009	20		PA		0-11	23-32-52		D10483		7		SM00001			S	YD158-YD170
001CO				AA	0-0	23-32-61		D10303		=C1		D10497		=C1		YC051-YD157
001CO				AA	0-0	23-32-52		D10279		=C1		D10485		=C1		YD158-YD170
001CX			0F	AA	15-11	23-32-61		D10303		=A1	5P	D10497		=A1		YC051-YC062
001CX			0F	AA	18-0	23-32-61		D10303		=A1	5M	D10497		=A1		YC063-YD157
001CX			0F	AA	21-1	23-32-52		D10279		=A1	5M	D10485		=A1		YD158-YD170
W3057	286A3057				PSU MOUNTED LCD VIDEO MONITOR NO.29 TO VDU IN CLUSTER NO.4											
0001	20		GA		13-6	23-32-62		D10309		1		D10501		1		YC051-YC062
0001	20		PA		14-10	23-32-62		D10309		1		D10501		1		YC063-YD157
0001	20		PA		23-4	23-32-61		D10301		1		D10489		1		YD158-YD170
0002	20		GA		13-6	23-32-62		D10309		2		D10501		4		YC051-YC062
0002	20		PA		14-10	23-32-62		D10309		2		D10501		4		YC063-YD157
0002	20		PA		23-4	23-32-61		D10301		2		D10489		4		YD158-YD170
0003	22		GA		13-6	23-32-62		D10309		10		D10501		2		YC051-YC062
0003	22		PA		14-10	23-32-62		D10309		10		D10501		2		YC063-YD157
0003	22		PA		23-4	23-32-61		D10301		10		D10489		2		YD158-YD170
0004	24		GK		13-6	23-32-62		D10309		6		D10501		8		YC051-YC062
0004	24		PK		14-10	23-32-62		D10309		6		D10501		8		YC063-YD157
0004	24		PK		23-4	23-32-61		D10301		6		D10489		8		YD158-YD170
0005	22		GA		13-6	23-32-62		D10309		9		D10501		3		YC051-YC062
0005	22		PA		14-10	23-32-62		D10309		9		D10501		3		YC063-YD157

WIRE LIST

D280A108

91-21-11

Section W3050

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3057		286A3057				PSU MOUNTED LCD VIDEO MONITOR NO.29 TO VDU IN CLUSTER NO.4 (continued)										
0005		20		PA		23-0	23-32-61	D10301		9		SM00001		S		YD158-YD170
0006		20		PA		0-11	23-32-61	D10489		3		SM00001		S		YD158-YD170
0007		22		GA		13-6	23-32-62	D10309		4		D10501	5			YC051-YC062
0007		22		PA		14-10	23-32-62	D10309		4		D10501	5			YC063-YD157
0007		20		PA		0-11	23-32-61	D10489		5		SM00001		S		YD158-YD170
0008		22		GA		13-6	23-32-62	D10309		7		D10501	6			YC051-YC062
0008		22		PA		14-10	23-32-62	D10309		7		D10501	6			YC063-YD157
0008		20		PA		0-11	23-32-61	D10489		6		SM00001		S		YD158-YD170
0009		22		GA		13-6	23-32-62	D10309		8		D10501	7			YC051-YC062
0009		22		PA		14-10	23-32-62	D10309		8		D10501	7			YC063-YD157
0009		20		PA		0-11	23-32-61	D10489		7		SM00001		S		YD158-YD170
001CO					AA	0-0	23-32-62	D10309	=C1			D10503	=C1			YC051-YD157
001CO					AA	0-0	23-32-61	D10301	=C1			D10491	=C1			YD158-YD170
001CX				OF	AA	13-0	23-32-62	D10309	=A1	5P		D10503	=A1			YC051-YC062
001CX				OF	AA	14-4	23-32-62	D10309	=A1	5M		D10503	=A1			YC063-YD157
001CX				OF	AA	22-10	23-32-61	D10301	=A1	5M		D10491	=A1			YD158-YD170
W3058		286A3058				ATT PANEL SHIP WIRE BUNDLE										
0002		22		PA		1-0	23-42-11	SM00002			S	D40170J	6			YC051-YD158, YL951-YN260
0003		22		PA		1-0	23-42-11	SM00001			S	D40170J	15			YC051-YD158, YL951-YR328
0004		22		PA		1-0	23-42-11	SM00009			S	D40170J	16			YC051-YD158, YL951-YR328
0005		22		PA		4-10	23-42-11	SM00004			S	D40170J	30			YC051-YD158, YL951-YR328
0006		22		PA		8-1	52-51-11	D40226P		11		SP03076		S		YC051-YD154
0007		20		PA		11-2	52-51-11	GD11106	DC..	1		SP03078		S		YC051-YD154
0011		20		PA		1-0	33-51-12	D40020P		3		SM00042		S		YD158, YL951-YL999
0012		22		PA		1-0	23-42-11	SM00012			S	D40170J	29			YC051-YD158, YL951-YR328
0020		22		PA		6-0	24-23-51	D11064		20		D40226P	1			YC051-YD158, YL951-YN260
0020		22		PA		6-1	24-23-51	D14364		20		D40226P	1			YN501-YR328
0021		20		PA		3-7	24-23-51	D11064		21		GD04164	DC..	1		YC051-YD158, YL951-YN260
0021		20		PA		3-8	24-23-51	D14364		21		GD04164	DC..	1		YN501-YR328
0025		18		PA		9-3	33-24-22	D41074P		1		D07168J	= 1	VY		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W3050

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3058	286A3058				ATT PANEL SHIP WIRE BUNDLE (continued)										
0027	24		PK		13-0	52-71-11	SP00533		9		D40170J	26			YL951-YL999, YN501-YR328
0027	24		PK		13-1	52-71-11	SP00533		9		D40170J	26			YN231-YN260
0028	24		PK		3-0	52-71-11	SP00533		9		SP00535		9		YC051-YD158, YL951-YR328
0029	22		PA		14-0	52-71-11	SP00537		9		GD04170	DC..	1		YC051-YD158
0029	22		PA		13-10	52-71-11	SP00537		9		GD04170	DC..	1A		YL951-YR328
0033	24		PK		14-10	33-22-11	D40052P		3		SM00014		S		YC051-YD158, YL951-YL999
0033	24		PK		15-0	33-22-11	D40052P		3		SM00014		S		YN231-YN260
0035	24		PK		1-0	33-22-11	D40052P		5		SM00015		S		YC051-YD158, YL951-YL999
0035	24		PK		1-1	33-22-11	D40052P		5		SM00015		S		YN231-YN260
0036	24		PK		1-0	33-22-11	D40052P		6		SM00016		S		YC051-YD158, YL951-YL999
0036	24		PK		1-1	33-22-11	D40052P		6		SM00016		S		YN231-YN260
0043	24		PK		5-5	33-22-11	D42008P		3		SM00014		S		YC051-YD158, YL951-YN260
0045	24		PK		15-1	33-22-11	D42008P		5		SM00015		S		YC051-YD158, YL951-YL999
0045	24		PK		15-2	33-22-11	D42008P		5		SM00015		S		YN231-YN260
0046	24		PK		15-1	33-22-11	D42008P		6		SM00016		S		YC051-YD158, YL951-YL999
0046	24		PK		15-2	33-22-11	D42008P		6		SM00016		S		YN231-YN260
0047	22		PA		6-5	23-42-11	D11064		39		SP00613		9		YL951-YN260
0047	22		PA		6-6	23-42-11	D14364		39		SP00613		9		YN501-YR328
0048	22		PA		6-5	23-42-11	D11064		34		SP00617		9		YL951-YN260
0048	22		PA		6-6	23-42-11	D14364		34		SP00617		9		YN501-YR328
0049	22		PA		6-5	23-42-11	D11064		33		SP00621		9		YL951-YN260
0049	22		PA		6-6	23-42-11	D14364		33		SP00621		9		YN501-YR328
0053	20		PA		5-2	33-26-31	D41074P		9		D07164J	= 1	VY		YN501-YR328
0054	18		PA		5-5	33-26-31	D41074P		8		GD03770	AC..	1		YN501-YR328
0055	20		PA		12-11	33-26-11	D41082P		15		GD04170	AC..	1A		YN501-YR328
0056	22		PA		15-3	33-26-11	D14364		22		D41082P		16		YN501-YR328
0060	20		PA		4-6	38-32-13	SP03060			S	D40148P		10		YC051-YD158, YL951-YL999, YN501-YR328
0060	20		PA		4-7	38-32-13	SP03060			S	D40148P		10		YN231-YN260
0061	24		PK		3-2	26-14-11	D40090J		6		SM00029		S		YC051-YD158

WIRE LIST

D280A108

91-21-11

Section W3050

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3058		286A3058			ATT PANEL SHIP WIRE BUNDLE (continued)											
0062		24		PK		17-6	33-29-11	D41082P			5	D40226P		5		YN501-YR328
0063		20		PA		12-10	33-29-11	D41082P			6	GD03926	DC..	1		YN501-YR328
0064		22		PA		6-1	33-26-11	D14364			23	SM00011		S		YN501-YR328
0067		22		PA		70-0	33-26-11	D14372			23	SM00011		S		YN501
0067		22		PA		89-3	33-26-11	D14372			23	SM00011		S		YR301-YR328
0069		22		PA		3-10	33-26-11	D14372			22	SP03522		S		YN501-YR328
0077		22		PA		1-0	23-42-11	D40170J			27	SM00077		S		YC051-YD157
0083		18		PA		4-7	33-24-21	D41072P			5	GD03926	ST..	1		YN501-YR328
0084		18		PA		4-7	33-24-21	D41072P			2	GD03926	AC..	1		YN501-YR328
0085		18		PA		4-7	33-24-21	D41072P			3	GD03926	ST..	1		YN501-YR328
0086		18		PA		4-7	33-24-21	D41072P			4	GD03926	AC..	1		YN501-YR328
0087		18		PA		9-10	33-24-21	D41072P			1	D07166J	=1	VY		YN501-YR314
0087		18		PA		9-10	33-24-21	D41072P			1	D07166J	=1	VS		YR315-YR328
0088		18		PA		4-8	33-24-21	D41072P			6	GD04170	AC..	1D		YN501-YR328
0089		18		PA		4-8	33-24-21	D41072P			7	GD04170	ST..	1D		YN501-YR328
0090		18		PA		4-8	33-24-21	D41072P			8	GD04170	AC..	1D		YN501-YR328
0091		18		PA		4-8	33-24-21	D41072P			9	GD04170	ST..	1D		YN501-YR328
0092		18		PA		11-4	33-24-22	D41074P			5	GD03998	ST..	1		YN501-YR328
0093		18		PA		11-4	33-24-22	D41074P			2	GD03998	AC..	1		YN501-YR328
0094		18		PA		11-4	33-24-22	D41074P			3	GD03998	ST..	1		YN501-YR328
0095		18		PA		11-4	33-24-22	D41074P			4	GD03998	AC..	1		YN501-YR328
0096		18		PA		11-4	33-24-22	D41074P			6	GD03998	AC..	1		YN501-YR328
0097		18		PA		11-4	33-24-22	D41074P			7	GD03998	ST..	1		YN501-YR328
0098		22		PA		4-8	23-42-14	SP00817		S		TB0954Y	B003	1A		YN501
0098		22		PA		4-9	23-42-14	SP00817		S		TB0954Y	B003	1A		YR301-YR328
0102		18		PA		2-1	33-24-22	D41078P		A		GD11098	ST..	1		YN501-YR328
0103		18		PA		2-1	33-24-22	D41078P		C		GD11098	AC..	1		YN501-YR328
0120		24		PK		3-8	26-14-11	D11068			20	D40090J		7		YC051-YD158
0121		24		PK		3-8	26-14-11	D11068			21	D40090J		8		YC051-YD158
0122		24		PK		3-8	26-14-11	D11068			22	D40090J		9		YC051-YD158
0125		24		PK		3-8	26-14-11	D11068			25	D40090J		4		YC051-YD158
0126		24		PK		3-8	26-14-11	D11068			26	D40090J		5		YC051-YD158
0127		24		PK		3-8	26-14-11	D11068			27	D40090J		2		YC051-YD158
0128		24		PK		3-8	26-14-11	D11068			28	D40090J		10		YC051-YD158
0129		24		PK		1-1	26-14-11	D11068			29	SM00029		S		YC051-YD158
0130		24		PK		5-5	26-14-11	D11068			30	D40226P		10		YC051-YD158
0131		20		PA		3-5	26-14-11	D11068			31	GD04164	DC..	1		YC051-YD158
0132		24		PK		1-1	26-14-11	D11068			32	SM00029		S		YC051-YD158
0133		20		PA		3-5	26-14-11	D11068			33	GD04164	DC..	1		YC051-YD158

WIRE LIST

D280A108

91-21-11

Section W3050

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3058	286A3058				ATT PANEL SHIP WIRE BUNDLE (continued)										
0134	24		PK		3-8	26-14-11	D11068				D40090J	1			YC051-YD158
0139	22		PA		6-4	23-42-11	D11068				SM00009		S		YC051-YD158, YL951-YN260
0139	22		PA		6-5	23-42-11	D14368				SM00009		S		YN501-YR328
0141	22		PA		6-4	23-42-11	D11068				SM00001		S		YC051-YD158, YL951-YN260
0141	22		PA		6-5	23-42-11	D14368				SM00001		S		YN501-YR328
0144	22		PA		2-1	23-42-11	D11068				SM00004		S		YC051-YD158, YL951-YN260
0144	22		PA		2-1	23-42-11	D14368				SM00004		S		YN501-YR328
0145	22		PA		2-1	23-42-11	D11068				SM00004		S		YC051-YD157
0146	22		PA		6-10	23-42-11	D11068				D40170J	5			YC051-YD158, YL951-YN260
0146	22		PA		6-11	23-42-11	D14368				D40170J	5			YN501-YR328
0147	22		PA		96-5	23-42-11	D11068				D40026P	15			YC051-YD158, YL951-YL999
0147	22		PA		77-1	23-42-11	D11068				D40026P	15			YN231-YN260
0147	22		PA		77-2	23-42-11	D14368				D40026P	15			YN501
0147	22		PA		96-5	23-42-11	D14368				D40026P	15			YR301-YR328
0148	22		PA		2-1	23-42-11	D11068				SM00008		S		YC051-YD158, YL951-YN260
0148	22		PA		2-1	23-42-11	D14368				SM00008		S		YN501-YR328
0149	22		PA		92-2	23-42-11	D11068				D11070	49			YC051-YD158, YL951-YL999
0149	22		PA		72-10	23-42-11	D11068				D11070	49			YN231-YN260
0149	22		PA		73-0	23-42-11	D14368				D14376	49			YN501
0149	22		PA		92-3	23-42-11	D14368				D14376	49			YR301-YR328
0151	22		PA		6-4	23-42-11	SM00077			S	D11068	51			YC051-YD157
0152	22		PA		6-4	23-42-11	D11068				SM00002		S		YC051-YD158, YL951-YN260
0153	20		PA		3-5	23-42-11	D11068				GD04164	DC..	1		YC051-YD158, YL951-YN260
0154	22		PA		92-2	23-42-11	D11068				D11070	54			YC051-YD158, YL951-YL999
0154	22		PA		72-10	23-42-11	D11068				D11070	54			YN231-YN260
0154	22		PA		73-0	23-42-11	D14368				D14376	54			YN501
0154	22		PA		92-3	23-42-11	D14368				D14376	54			YR301-YR328
0155	20		PA		3-2	23-42-11	D11068				GD04168	DC..	1		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W3050

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3058		286A3058			ATT PANEL SHIP WIRE BUNDLE (continued)											
0161		22		PA		6-4	23-42-11	D11068	61			SM00012		S		YC051-YD158, YL951-YN260
0161		22		PA		6-5	23-42-11	D14368	61			SM00012		S		YN501-YR328
0163		24		PK		6-7	33-29-11	D14364	27			D40054J	7			YN501-YR328
0164		24		PK		3-2	33-29-11	D14364	26			D12416	1			YN501-YR328
0166		22		PA		71-11	23-42-15	SP00817		S		TB0952Y	B011	1A		YN501
0166		22		PA		91-1	23-42-15	SP00817		S		TB0952Y	B011	1A		YR301-YR328
0170		22		PA		4-6	23-42-14	D40226P	20			SM00044		S		YN501-YR328
0171		22		PA		1-9	23-42-14	D14370	1			SM00044		S		YN501-YR328
0172		20		PA		6-6	23-42-14	D14370	2			GD04164	DC..	1		YN501-YR328
0173		20		PA		6-6	23-42-14	D14370	3			GD04164	ST..	1		YN501-YR328
0174		20		PA		6-6	23-42-14	D14364	10			GD04164	ST..	1		YN501-YR328
0175		20		PA		6-6	23-42-14	D14364	11			GD04164	ST..	1		YN501-YR328
0176		22		PA		4-8	23-42-14	SP00831		S		TB0954Y	B001	1A		YN501
0176		22		PA		4-9	23-42-14	SP00831		S		TB0954Y	B001	1A		YR301-YR328
0177		22		PA		71-3	23-42-15	D14378	1			SM00044		S		YN501
0177		22		PA		90-6	23-42-15	D14378	1			SM00044		S		YR301-YR328
0180		20		PA		6-6	23-42-15	D14378	2			GD04223	DC..	1		YN501-YR328
0181		20		PA		6-6	23-42-15	D14378	3			GD04223	ST..	1		YN501-YR328
0182		20		PA		6-6	23-42-15	D14372	10			GD04223	ST..	1		YN501-YR328
0183		20		PA		6-6	23-42-15	D14372	11			GD04223	ST..	1		YN501-YR328
0187		22		PA		71-11	23-42-15	SP00831		S		TB0952Y	B009	1A		YN501
0187		22		PA		91-1	23-42-15	SP00831		S		TB0952Y	B009	1A		YR301-YR328
0188		22		PA		75-4	33-51-11	D14372	31			D40226P	19			YN501
0188		22		PA		94-7	33-51-11	D14372	31			D40226P	19			YR301-YR328
0189		24		PK		26-9	23-42-14	D14370	36			D43922P	B04			YN501-YR328
0190		22		PA		25-6	23-42-14	D43922P	A04			SM00044		S		YN501-YR328
0191		22		PA		24-9	23-42-14	D43922P	A03			SP00831		S		YN501-YR328
0197		22		PA		6-6	23-42-11	D14364	32			SP00869		9		YN501-YR315
0197		22		PA		6-6	23-42-11	D14364	32			SP00595		9		YR316-YR328
0201		22		PA		11-3	38-41-11	D11070	1			D40148P	1			YC051-YD158, YL951-YL999
0201		22		PA		11-8	38-41-11	D11070	1			D40148P	1			YN231-YN260
0202		22		PA		11-3	38-41-11	D11070	2			D40148P	2			YC051-YD158, YL951-YL999
0202		22		PA		11-8	38-41-11	D11070	2			D40148P	2			YN231-YN260
0203		22		PA		10-9	38-41-11	D11070	3			SM00003		S		YC051-YD158, YL951-YL999
0203		22		PA		11-2	38-41-11	D11070	3			SM00003		S		YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W3050

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3058	286A3058				ATT PANEL SHIP WIRE BUNDLE (continued)										
0204	20		PA		3-8	38-41-11	D11070		4		GD03948	DC..	1		YC051-YD158, YL951-YN260
0205	22		PA		11-3	38-32-13	D11070		5		D40148P		5		YC051-YD158, YL951-YL999
0205	22		PA		11-8	38-32-13	D11070		5		D40148P		5		YN231-YN260
0206	22		PA		11-3	38-32-13	D11070		6		D40148P		7		YC051-YD158, YL951-YL999
0206	22		PA		11-8	38-32-13	D11070		6		D40148P		7		YN231-YN260
0207	20		PA		3-8	38-32-13	D11070		7		GD03948	DC..	1		YC051-YD158, YL951-YN260
0208	20		PA		11-3	38-32-13	D11070		8		SP03060			S	YC051-YD158, YL951-YN260
0209	20		PA		11-3	38-32-13	D11070		9		D40148P		8		YC051-YD158, YL951-YL999
0209	20		PA		11-8	38-32-13	D11070		9		D40148P		8		YN231-YN260
0210	20		PA		3-8	38-32-13	D11070		10		GD03948	DC..	1		YC051-YD158, YL951-YN260
0211	22		PA		11-3	38-32-13	D11070		11		D40148P		9		YC051-YD158, YL951-YL999
0211	22		PA		11-8	38-32-13	D11070		11		D40148P		9		YN231-YN260
0212	20		PA		11-3	38-32-13	D11070		12		D40148P		4		YC051-YD158, YL951-YL999
0212	20		PA		11-8	38-32-13	D11070		12		D40148P		4		YN231-YN260
0227	20		PA		11-4	38-32-13	D14376		8		SP03060			S	YN501-YR328
0228	22		PA		11-4	38-32-13	D14376		5		D40148P		5		YN501-YR328
0229	22		PA		11-4	38-32-13	D14376		6		D40148P		7		YN501-YR328
0230	20		PA		11-4	38-32-13	D14376		12		D40148P		4		YN501-YR328
0231	20		PA		11-4	38-32-13	D14376		9		D40148P		8		YN501-YR328
0232	22		PA		11-4	38-32-13	D14376		11		D40148P		9		YN501-YR328
0233	20		PA		3-8	38-32-13	D14376		4		GD03948	DC..	1		YN501-YR328
0234	22		PA		10-10	38-41-11	D14376		3		SM00003			S	YN501-YR328
0239	22		PA		88-8	23-42-11	D11070		39		SM00009			S	YC051-YD158, YL951-YL999
0239	22		PA		69-5	23-42-11	D11070		39		SM00009			S	YN231-YN260
0239	22		PA		69-6	23-42-11	D14376		39		SM00009			S	YN501
0239	22		PA		88-9	23-42-11	D14376		39		SM00009			S	YR301-YR328
0240	22		PA		11-4	38-41-11	D14376		1		D40148P		1		YN501-YR328
0241	22		PA		88-8	23-42-11	D11070		41		SM00001			S	YC051-YD158, YL951-YL999

WIRE LIST

D280A108

91-21-11

Section W3050

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3058		286A3058			ATT PANEL SHIP WIRE BUNDLE (continued)											
0241		22		PA		69-5	23-42-11	D11070	41			SM00001		S		YN231-YN260
0241		22		PA		69-6	23-42-11	D14376	41			SM00001		S		YN501
0241		22		PA		88-9	23-42-11	D14376	41			SM00001		S		YR301-YR328
0243		22		PA		11-4	38-41-11	D14376	2			D40148P	2			YN501-YR328
0244		22		PA		90-8	23-42-11	D11070	44			SM00004		S		YC051-YD158, YL951-YL999
0244		22		PA		71-4	23-42-11	D11070	44			SM00004		S		YN231-YN260
0244		22		PA		71-5	23-42-11	D14376	44			SM00004		S		YN501
0244		22		PA		90-8	23-42-11	D14376	44			SM00004		S		YR301-YR328
0245		22		PA		4-4	23-42-14	D14370	47			TB0954Y	A001	1A		YN501
0245		22		PA		4-5	23-42-14	D14370	47			TB0954Y	A001	1A		YR301-YR328
0246		22		PA		4-4	23-42-14	D14370	50			TB0954Y	A003	1A		YN501
0246		22		PA		4-5	23-42-14	D14370	50			TB0954Y	A003	1A		YR301-YR328
0248		22		PA		90-8	23-42-11	D11070	48			SM00008		S		YC051-YD158, YL951-YL999
0248		22		PA		71-4	23-42-11	D11070	48			SM00008		S		YN231-YN260
0248		22		PA		71-5	23-42-11	D14376	48			SM00008		S		YN501
0248		22		PA		90-8	23-42-11	D14376	48			SM00008		S		YR301-YR328
0249		22		PA		4-11	23-42-15	D14378	47			TB0952Y	A009	1A		YN501-YR328
0251		22		PA		88-8	23-42-11	SM00077		S		D11070	51			YC051-YD157
0252		22		PA		88-8	23-42-11	D11070	52			SM00002		S		YC051-YD158, YL951-YL999
0252		22		PA		69-5	23-42-11	D11070	52			SM00002		S		YN231-YN260
0253		20		PA		3-8	23-42-11	D11070	53			GD03948	DC..	1		YC051-YD158, YL951-YN260
0255		20		PA		3-8	23-42-11	D11070	56			GD03948	DC..	1		YC051-YD158, YL951-YN260
0255		20		PA		3-8	23-42-11	D14376	56			GD03948	DC..	1		YN501-YR328
0256		20		PA		3-8	23-42-11	D11070	55			GD03948	DC..	1		YC051-YD157
0261		22		PA		88-8	23-42-11	D11070	61			SM00012		S		YC051-YD158, YL951-YL999
0261		22		PA		69-5	23-42-11	D11070	61			SM00012		S		YN231-YN260
0261		22		PA		69-6	23-42-11	D14376	61			SM00012		S		YN501
0261		22		PA		88-9	23-42-11	D14376	61			SM00012		S		YR301-YR328
0263		22		PA		1-0	38-41-11	D40148P	3			SM00003		S		YC051-YD158, YL951-YL999, YN501-YR328
0263		22		PA		1-1	38-41-11	D40148P	3			SM00003		S		YN231-YN260
0266		22		PA		4-11	23-42-15	D14378	50			TB0952Y	A011	1A		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W3050

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W3058	286A3058				ATT PANEL SHIP WIRE BUNDLE (continued)											
0284	20		PA		89-9	SPARE		D40054J		5		D11070	CAP	Y		YC051-YD158, YL951-YL999
0284	20		PA		70-5	SPARE		D40054J		5		D11070	CAP	Y		YN231-YN260
0284	20		PA		70-6	SPARE		D40054J		5		D14376	CAP	Y		YN501
0284	20		PA		89-9	SPARE		D40054J		5		D14376	CAP	Y		YR301-YR328
0285	20		PA		89-9	SPARE		D40054J		6		D11070	CAP	Y		YC051-YD158, YL951-YL999
0285	20		PA		70-5	SPARE		D40054J		6		D11070	CAP	Y		YN231-YN260
0285	20		PA		70-6	SPARE		D40054J		6		D14376	CAP	Y		YN501
0285	20		PA		89-9	SPARE		D40054J		6		D14376	CAP	Y		YR301-YR328
0286	20		PA		89-9	SPARE		D40054J		8		D11070	CAP	Y		YC051-YD158, YL951-YL999
0286	20		PA		70-5	SPARE		D40054J		8		D11070	CAP	Y		YN231-YN260
0286	20		PA		70-6	SPARE		D40054J		8		D14376	CAP	Y		YN501
0286	20		PA		89-9	SPARE		D40054J		8		D14376	CAP	Y		YR301-YR328
0291	22		PA		1-1	33-26-11		D40054J		1		SM00011		S		YC051-YD158, YL951-YR328
0293	22		PA		83-0	38-41-11		D40054J		3		SM00003		S		YC051-YD158, YL951-YL999, YR301-YR328
0293	22		PA		63-8	38-41-11		D40054J		3		SM00003		S		YN231-YN260
0293	22		PA		63-9	38-41-11		D40054J		3		SM00003		S		YN501
0294	24		PK		4-4	33-29-11		D40054J		4		SM00024		S		YC051-YD158, YL951-YN260
0297	24		PK		6-6	33-29-11		D40054J		7		D11064		27		YC051-YD158, YL951-YN260
0301	22		PA		6-6	33-22-11		D11064		1		D40054J		10		YC051-YD158, YL951-YN260
0302	24		PK		6-6	33-22-11		D11064		2		D40054J		2		YC051-YD158, YL951-YN260
0302	22		PA		3-11	33-22-11		D40050J		2		D40054J		2		YN501-YR328
0303	24		PK		2-2	33-22-11		D11064		3		SM00014		S		YC051-YD158, YL951-YN260
0304	24		PK		16-0	33-22-11		D11064		4		SM00015		S		YC051-YD158, YL951-YL999
0304	24		PK		16-1	33-22-11		D11064		4		SM00015		S		YN231-YN260
0305	20		PA		3-7	33-22-11		D11064		5		GD04164	AC..	1		YC051-YD158, YL951-YN260

WIRE LIST

D280A108

91-21-11

Section W3050

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W3058	286A3058				ATT PANEL SHIP WIRE BUNDLE (continued)											
0306	24		PK		7-0	33-21-11	D11064		6		D40050J		2		YC051-YD158, YL951-YN260	
0307	20		PA		11-9	33-21-11	D11064		7		D07174J	= 1	VY		YC051-YD158, YL951-YN260	
0308	24		PK		7-0	33-21-11	D11064		8		D40050J		1		YC051-YD158, YL951-YN260	
0309	20		PA		3-7	33-21-11	D11064		9		GD04164	AC..	1		YC051-YD158, YL951-YN260	
0310	18		PA		3-7	33-29-11	D11064		10	18	GD04164	ST..	1		YC051-YD158, YL951-YN260	
0311	18		PA		3-7	33-29-11	D11064		11	18	GD04164	ST..	1		YC051-YD158, YL951-YN260	
0312	24		PK		7-8	33-29-11	D11064		12		D40020P		1		YC051-YD158, YL951-YN260	
0313	24		PK		7-8	33-29-11	D11064		13		D40020P		7		YC051-YD158, YL951-YN260	
0314	24		PK		2-2	33-29-11	D11064		14		SM00024			S	YC051-YD158, YL951-YN260	
0315	24		PK		7-8	33-29-11	D11064		15		D40020P		8		YC051-YD158, YL951-YN260	
0316	24		PK		7-8	33-29-11	D11064		16		D40020P		13		YC051-YD158, YL951-YN260	
0320	20		PA		5-4	SPARE	D40226P	CAP	Y		GD11106	ST..	1		YD155-YD158, YL951-YR328	
0322	22		PA		7-8	33-26-11	D11064		22		D40020P		16		YC051-YD158, YL951-YN260	
0323	22		PA		6-0	33-26-11	D11064		23		SM00011			S	YC051-YD158, YL951-YN260	
0324	20		PA		3-7	33-26-11	D11064		24		GD04164	AC..	1		YC051-YD158, YL951-YN260	
0326	20		PA		3-0	33-29-11	D11064		26		D12416		1		YC051-YD158, YL951-YN260	
0331	24		PK		16-0	33-22-11	D11064		31		SM00016			S	YC051-YD158, YL951-YL999	
0331	24		PK		16-1	33-22-11	D11064		31		SM00016			S	YN231-YN260	
0332	20		PA		3-7	33-22-11	D11064		32		GD04164	AC..	1		YC051-YD158, YL951-YN260	
0362	20		PA		3-3	33-29-11	D40020P		2		GD03926	AC..	1		YC051-YD158, YL951-YN260	

WIRE LIST

D280A108

91-21-11

Section W3050

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3058	286A3058				ATT PANEL SHIP WIRE BUNDLE (continued)										
0363	20		PA		5-2	33-51-12	D40020P	3			SP03480		S		YC051-YD157, YN231-YN260
0363	16		PA		4-5	33-51-12	SM00042		S		SP03480		S		YD158, YL951-YL999
0363	20		PA		12-9	33-51-12	D41082P	3			SP03480		9		YN501-YR328
0364	20		PA		3-4	33-51-12	D40020P	4			GD04170	DC..	1A		YC051-YD158, YL951-YN260
0364	20		PA		12-11	33-51-12	D41082P	4			GD04170	DC..	1A		YN501-YR328
0365	24		PK		10-0	33-29-11	D40020P	5			D40226P		5		YC051-YD158, YL951-YN260
0366	20		PA		3-3	33-29-11	D40020P	6			GD03926	DC..	1		YC051-YD158, YL951-YN260
0369	22		PA		6-0	23-42-11	D40020P	9			SM00008		S		YC051-YD158, YL951-YN260
0369	22		PA		13-6	23-42-11	D41082P	9			SM00008		S		YN501-YR328
0370	20		PA		3-4	23-42-11	D40020P	10			GD04170	DC..	1A		YC051-YD158, YL951-YN260
0370	20		PA		12-11	23-42-11	D41082P	10			GD04170	DC..	1A		YN501-YR328
0371	22		PA		5-2	33-27-11	D40020P	11			SP02990		S		YC051-YD158, YL951-YN260
0371	22		PA		12-9	33-27-11	D41082P	11			SP02990		S		YN501-YR328
0372	22		PA		5-2	33-27-11	D40020P	12			SP03498		S		YC051-YD158, YL951-YN260
0372	22		PA		12-9	33-27-11	D41082P	12			SP03498		S		YN501-YR328
0373	20		PA		3-5	33-29-11	D12416	2			GD04164	AC..	1		YC051-YD158, YL951-YR328
0374	20		PA		3-3	33-29-11	D40020P	14			GD03926	ST..	1		YC051-YD158, YL951-YN260
0375	20		PA		3-4	33-26-11	D40020P	15			GD04170	AC..	1A		YC051-YD158, YL951-YN260
0381	20		PA		9-3	SPARE	D40226P	8			D40050J		8		YC051-YD158, YL951-YR328
0382	20		PA		9-3	SPARE	D40226P	9			D40050J		9		YC051-YD158, YL951-YR328
0383	20		PA		9-3	SPARE	D40226P	12			D40050J		11		YC051-YD158, YL951-YR328
0387	20		PA		89-2	SPARE	D40170J	18			D11066	CAP	Y		YC051-YD158, YL951-YL999
0387	20		PA		69-11	SPARE	D40170J	18			D11066	CAP	Y		YN231-YN260
0387	20		PA		70-0	SPARE	D40170J	18			D14372	CAP	Y		YN501

WIRE LIST

D280A108

91-21-11

Section W3050

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type
W3058	286A3058			ATT PANEL SHIP WIRE BUNDLE (continued)										
0387	20	PA		89-2	SPARE	D40170J	18			D14372	CAP	Y		YR301-YR328
0388	20	PA		89-2	SPARE	D40170J	19			D11066	CAP	Y		YC051-YD158, YL951-YL999
0388	20	PA		69-11	SPARE	D40170J	19			D11066	CAP	Y		YN231-YN260
0388	20	PA		70-0	SPARE	D40170J	19			D14372	CAP	Y		YN501
0388	20	PA		89-2	SPARE	D40170J	19			D14372	CAP	Y		YR301-YR328
0389	20	PA		89-2	SPARE	D40170J	31			D11066	CAP	Y		YC051-YD158, YL951-YL999
0389	20	PA		69-11	SPARE	D40170J	31			D11066	CAP	Y		YN231-YN260
0389	20	PA		70-0	SPARE	D40170J	31			D14372	CAP	Y		YN501
0389	20	PA		89-2	SPARE	D40170J	31			D14372	CAP	Y		YR301-YR328
0410	18	PA		8-3	33-29-11	D11066	10	18		GD03770	ST..	1		YC051-YD158, YL951-YL999
0410	18	PA		8-2	33-29-11	D11066	10	18		GD03770	ST..	1		YN231-YN260
0411	18	PA		8-3	33-29-11	D11066	11	18		GD03770	ST..	1		YC051-YD158, YL951-YL999
0411	18	PA		8-2	33-29-11	D11066	11	18		GD03770	ST..	1		YN231-YN260
0412	24	PK		8-1	33-29-11	D11066	12			D40026P		1		YC051-YD158, YL951-YL999
0412	24	PK		8-2	33-29-11	D11066	12			D40026P		1		YN231-YN260
0413	24	PK		8-1	33-29-11	D11066	13			D40026P		7		YC051-YD158, YL951-YL999
0413	24	PK		8-2	33-29-11	D11066	13			D40026P		7		YN231-YN260
0414	24	PK		90-7	33-29-11	D11066	14			SM00024			S	YC051-YD158, YL951-YL999
0414	24	PK		71-4	33-29-11	D11066	14			SM00024			S	YN231-YN260
0415	24	PK		8-1	33-29-11	D11066	15			D40026P		8		YC051-YD158, YL951-YL999
0415	24	PK		8-2	33-29-11	D11066	15			D40026P		8		YN231-YN260
0416	24	PK		8-1	33-29-11	D11066	16			D40026P		13		YC051-YD158, YL951-YL999
0416	24	PK		8-2	33-29-11	D11066	16			D40026P		13		YN231-YN260
0422	22	PA		3-9	33-26-11	D11066	22			SP03522			S	YC051-YD158, YL951-YL999
0422	22	PA		3-10	33-26-11	D11066	22			SP03522			S	YN231-YN260
0423	22	PA		89-2	33-26-11	D11066	23			SM00011			S	YC051-YD158, YL951-YL999
0423	22	PA		69-11	33-26-11	D11066	23			SM00011			S	YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W3050

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3058	286A3058				ATT PANEL SHIP WIRE BUNDLE (continued)										
0424	20		PA		8-3	33-26-11	D11066	24			GD03770	AC..	1		YC051-YD158, YL951-YL999
0424	20		PA		8-2	33-26-11	D11066	24			GD03770	AC..	1		YN231-YN260
0428	22		PA		89-2	33-51-11	D11066	28			D40170J	17			YC051-YD158, YL951-YL999
0428	22		PA		69-11	33-51-11	D11066	28			D40170J	17			YN231-YN260
0428	22		PA		70-0	33-51-11	D14372	28			D40170J	17			YN501
0428	22		PA		89-2	33-51-11	D14372	28			D40170J	17			YR301-YR328
0429	22		PA		89-2	33-51-11	D11066	29			D40170J	28			YC051-YD158, YL951-YL999
0429	22		PA		69-11	33-51-11	D11066	29			D40170J	28			YN231-YN260
0429	22		PA		70-0	33-51-11	D14372	29			D40170J	28			YN501
0429	22		PA		89-2	33-51-11	D14372	29			D40170J	28			YR301-YR328
0430	20		PA		8-3	33-51-11	D11066	30			GD03770	DC..	1		YC051-YD158, YL951-YL999
0430	20		PA		8-2	33-51-11	D11066	30			GD03770	DC..	1		YN231-YN260
0430	22		PA		8-4	33-51-11	D14372	30			GD03770	DC..	1		YN501-YR328
0462	20		PA		3-0	33-29-11	D40026P	2			GD03998	AC..	1		YC051-YD158, YL951-YL999
0462	20		PA		2-11	33-29-11	D40026P	2			GD03998	AC..	1		YN231-YN260
0463	20		PA		8-6	33-51-14	D40026P	3			SP03484		S		YC051-YD158, YL951-YR328
0464	20		PA		3-0	33-51-14	D40026P	4			GD03998	DC..	1		YC051-YD158, YL951-YL999, YN501-YR328
0464	20		PA		2-11	33-51-14	D40026P	4			GD03998	DC..	1		YN231-YN260
0465	24		PK		98-10	33-29-11	D40026P	5			D40226P	6			YC051-YD158, YL951-YL999, YR301-YR328
0465	24		PK		79-6	33-29-11	D40026P	5			D40226P	6			YN231-YN260
0465	24		PK		79-7	33-29-11	D40026P	5			D40226P	6			YN501
0466	20		PA		3-0	33-29-11	D40026P	6			GD03998	DC..	1		YC051-YD158, YL951-YL999, YN501-YR328
0466	20		PA		2-11	33-29-11	D40026P	6			GD03998	DC..	1		YN231-YN260
0469	22		PA		8-6	33-27-22	D40026P	9			SP03492		S		YC051-YD158, YL951-YR328
0470	22		PA		8-6	33-27-22	D40026P	10			SP03490		S		YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W3050

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W3058	286A3058			ATT PANEL SHIP WIRE BUNDLE (continued)												
0474	20		PA		3-0		33-29-11	D40026P	14			GD03998	ST..	1		YC051-YD158, YL951-YL999
0474	20		PA		2-11		33-29-11	D40026P	14			GD03998	ST..	1		YN231-YN260
0476	20		PA		3-0		23-42-11	D40026P	16			GD03998	DC..	1		YC051-YD158, YL951-YL999, YN501-YR328
0476	20		PA		2-11		23-42-11	D40026P	16			GD03998	DC..	1		YN231-YN260
0575	18		PA		9-9		SPARE	D41078P	B			D41074P	10			YN501-YR328
0576	18		PA		9-9		SPARE	D41078P	CAP	Y		D41074P	11			YN501-YR328
0577	18		PA		9-9		SPARE	D41078P	CAP	Y		D41074P	12			YN501-YR328
2001B	24		OT	EA	11-5		33-21-12	D41070P	2			D14370	22			YN501-YR328
2001W	24		OT	EA	0-0		33-21-12	D41070P	1			D14370	21			YN501-YR328
2001Z				EA	0-0		33-21-12	D41070P	5			D14370	23			YN501-YR328
2002B	24		PL	EB	11-5		33-21-12	D41070P	4			D14370	25			YN501-YR328
2002R	24		PL	EB	0-0		33-21-12	D41070P	3			D14370	24			YN501-YR328
2003B	24		OT	EC	13-0		33-22-31	D41062P	2			D14370	17			YN501-YR328
2003W	24		OT	EC	0-0		33-22-31	D41062P	1			D14370	16			YN501-YR328
2003Z				EC	0-0		33-22-31	D41062P	5			D14370	18			YN501-YR328
2004B	24		PL	ED	13-0		33-22-31	D41062P	4			D14370	20			YN501-YR328
2004R	24		PL	ED	0-0		33-22-31	D41062P	3			D14370	19			YN501-YR328
2005B	24		OT	EE	15-8		33-22-41	D41076P	2			D14370	12			YN501-YR328
2005W	24		OT	EE	0-0		33-22-41	D41076P	1			D14370	11			YN501-YR328
2005Z				EE	0-0		33-22-41	D41076P	5			D14370	13			YN501-YR328
2006B	24		PL	EF	15-8		33-22-41	D41076P	4			D14370	15			YN501-YR328
2006R	24		PL	EF	0-0		33-22-41	D41076P	3			D14370	14			YN501-YR328
2007B	24		OT	EG	4-6		33-24-21	D14612	2			D14370	5			YN501-YR328
2007W	24		OT	EG	0-0		33-24-21	D14612	1			D14370	4			YN501-YR328
2007Z				EG	0-0		33-24-21	D14612	5			D14370	6			YN501-YR328
2008B	24		PL	EH	4-6		33-24-21	D14612	4			D14370	8			YN501-YR328
2008R	24		PL	EH	0-0		33-24-21	D14612	3			D14370	7			YN501-YR328
2019B	24		OT	ET	72-6		23-42-14	D14370	27			D14378	27			YN501
2019B	24		OT	ET	91-8		23-42-14	D14370	27			D14378	27			YR301-YR328
2019W	24		OT	ET	0-0		23-42-14	D14370	26			D14378	26			YN501-YR328
2019Z				ET	0-0		23-42-14	D14370	28			D14378	28			YN501-YR328
2021B	24		Y2	EV	26-9		23-42-14	D14370	32			D43922P	B01			YN501-YR328
2021R	24		Y2	EV	0-0		23-42-14	D14370	31			D43922P	A01			YN501-YR328
2021Z				EV	0-0		23-42-14	D14370			AA	D43922P			AB	YN501-YR328
2022B	24		Y2	EW	26-9		23-42-14	D14370	34			D43922P	B02			YN501-YR328
2022R	24		Y2	EW	0-0		23-42-14	D14370	33			D43922P	A02			YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W3050

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From		Term	Type	Splice	To				Effectivity
	GA	CO	TY		FT-IN	Diagram	Equip	Equip				Term	Type	Splice		
W3058	286A3058			ATT PANEL SHIP WIRE BUNDLE (continued)												
2022Z				EW	0-0	23-42-14	D14370				AA	D43922P			AB	YN501-YR328
2218B	22	PB	KS		6-0	24-23-51	D11064		19			D40226P	3			YC051-YD158, YL951-YN260
2218B	22	PB	KS		6-1	24-23-51	D14364		19			D40226P	3			YN501-YR328
2218R	22	PB	KS		0-0	24-23-51	D11064		18			D40226P	2			YC051-YD158, YL951-YN260
2218R	22	PB	KS		0-0	24-23-51	D14364		18			D40226P	2			YN501-YR328
A-1					0-0	52-71-11	S01147		1			SP00537		9		YC051-YD158, YL951-YR328
A-2					0-0	52-71-11	S01147		2			SP00533		9		YC051-YD158, YL951-YR328
A-3					0-0	52-71-11	S01147		3			S01147	CAP	Y		YC051-YD158, YL951-YR328
A-4					0-0	52-71-11	SP00537			9		S01147	4			YC051-YD158, YL951-YR328
A-5					0-0	52-71-11	SP00535			9		S01147	5			YC051-YD158, YL951-YR328
A-6					0-0	52-71-11	S01147		6			S01147	CAP	Y		YC051-YD158, YL951-YR328
A-A					0-0	52-51-11	M00117			RED		SP03076			S	YC051-YD154
A-B					0-0	52-51-11	M00117			BLU		SP03078			S	YC051-YD154
FRAA					0-0	23-42-14	D14370				AA	D14370	35			YN501-YR328
FRAB					0-0	23-42-14	D43922P				AB	D43922P	PERG	1F		YN501-YR328
W3059	286A3059			PSU MOUNTED LCD VIDEO MONITOR NO.30 TO VDU IN CLUSTER NO.4												
0001	20	GA			18-10	23-32-62	D10311		1			D10507	1			YC051-YC062
0001	20	PA			19-9	23-32-62	D10311		1			D10507	1			YC063-YD157
0001	20	PA			28-4	23-32-61	D10303		1			D10495	1			YD158-YD170
0002	20	GA			18-10	23-32-62	D10311		2			D10507	4			YC051-YC062
0002	20	PA			19-9	23-32-62	D10311		2			D10507	4			YC063-YD157
0002	20	PA			28-4	23-32-61	D10303		2			D10495	4			YD158-YD170
0003	22	GA			18-10	23-32-62	D10311		10			D10507	2			YC051-YC062
0003	22	PA			19-9	23-32-62	D10311		10			D10507	2			YC063-YD157
0003	22	PA			28-4	23-32-61	D10303		10			D10495	2			YD158-YD170
0004	24	GK			18-10	23-32-62	D10311		6			D10507	8			YC051-YC062
0004	24	PK			19-9	23-32-62	D10311		6			D10507	8			YC063-YD157
0004	24	PK			28-4	23-32-61	D10303		6			D10495	8			YD158-YD170
0005	22	GA			18-10	23-32-62	D10311		9			D10507	3			YC051-YC062
0005	22	PA			19-9	23-32-62	D10311		9			D10507	3			YC063-YD157

WIRE LIST

D280A108

91-21-11

Section W3050

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3059	286A3059			PSU MOUNTED LCD VIDEO MONITOR NO.30 TO VDU IN CLUSTER NO.4 (continued)											
0005	20		PA		28-0	23-32-61	D10303		9		SM00001		S		YD158-YD170
0006	20		PA		0-10	23-32-61	D10495		3		SM00001		S		YD158-YD170
0007	22		GA		18-10	23-32-62	D10311		4		D10507	5			YC051-YC062
0007	22		PA		19-9	23-32-62	D10311		4		D10507	5			YC063-YD157
0007	20		PA		0-10	23-32-61	D10495		5		SM00001		S		YD158-YD170
0008	22		GA		18-10	23-32-62	D10311		7		D10507	6			YC051-YC062
0008	22		PA		19-9	23-32-62	D10311		7		D10507	6			YC063-YD157
0008	20		PA		0-10	23-32-61	D10495		6		SM00001		S		YD158-YD170
0009	22		GA		18-10	23-32-62	D10311		8		D10507	7			YC051-YC062
0009	22		PA		19-9	23-32-62	D10311		8		D10507	7			YC063-YD157
0009	20		PA		0-10	23-32-61	D10495		7		SM00001		S		YD158-YD170
001CO				AA	0-0	23-32-62	D10311	=C1			D10509	=C1			YC051-YD157
001CO				AA	0-0	23-32-61	D10303	=C1			D10497	=C1			YD158-YD170
001CX		0F		AA	18-5	23-32-62	D10311	=A1	5P		D10509	=A1			YC051-YC062
001CX		0F		AA	19-3	23-32-62	D10311	=A1	5M		D10509	=A1			YC063-YD157
001CX		0F		AA	27-10	23-32-61	D10303	=A1	5M		D10497	=A1			YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W3050

Page 17 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From		To			Effectivity						
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term		Type	Splice	Equip	Term	Type	Splice
I	W3061	286A3061			PSU MOUNTED LCD VIDEO MONITOR NO.31 TO VDU IN CLUSTER NO.4											
	0001	20		GA		23-0	23-32-63	D10317		1		D10513		1		YC051-YC062
I	0001	20		PA		23-2	23-32-63	D10317		1		D10513		1		YC063-YD157
	0002	20		GA		23-0	23-32-63	D10317		2		D10513		4		YC051-YC062
I	0002	20		PA		23-2	23-32-63	D10317		2		D10513		4		YC063-YD157
	0003	22		GA		23-0	23-32-63	D10317		10		D10513		2		YC051-YC062
I	0003	22		PA		23-2	23-32-63	D10317		10		D10513		2		YC063-YD157
	0004	24		GK		23-0	23-32-63	D10317		6		D10513		8		YC051-YC062
I	0004	24		PK		23-2	23-32-63	D10317		6		D10513		8		YC063-YD157
	0005	22		GA		23-0	23-32-63	D10317		9		D10513		3		YC051-YC062
I	0005	22		PA		23-2	23-32-63	D10317		9		D10513		3		YC063-YD157
	0007	22		GA		23-0	23-32-63	D10317		4		D10513		5		YC051-YC062
I	0007	22		PA		23-2	23-32-63	D10317		4		D10513		5		YC063-YD157
	0008	22		GA		23-0	23-32-63	D10317		7		D10513		6		YC051-YC062
I	0008	22		PA		23-2	23-32-63	D10317		7		D10513		6		YC063-YD157
	0009	22		GA		23-0	23-32-63	D10317		8		D10513		7		YC051-YC062
I	0009	22		PA		23-2	23-32-63	D10317		8		D10513		7		YC063-YD157
I	001CO			AA		0-0	23-32-63	D10317		=C1		D10515		=C1		YC051-YD157
	001CX			OF	AA	22-6	23-32-63	D10317		=A1	5P	D10515		=A1		YC051-YC062
I	001CX			OF	AA	22-8	23-32-63	D10317		=A1	5M	D10515		=A1		YC063-YD157
I	W3063	286A3063			PSU MOUNTED LCD VIDEO MONITOR NO.32 TO VDU IN CLUSTER NO.4											
	0001	20		GA		27-8	23-32-63	D10319		1		D10519		1		YC051-YC062
I	0001	20		PA		29-6	23-32-63	D10319		1		D10519		1		YC063-YD157
	0002	20		GA		27-8	23-32-63	D10319		2		D10519		4		YC051-YC062
I	0002	20		PA		29-6	23-32-63	D10319		2		D10519		4		YC063-YD157
	0003	22		GA		27-8	23-32-63	D10319		10		D10519		2		YC051-YC062
I	0003	22		PA		29-6	23-32-63	D10319		10		D10519		2		YC063-YD157
	0004	24		GK		27-8	23-32-63	D10319		6		D10519		8		YC051-YC062
I	0004	24		PK		29-6	23-32-63	D10319		6		D10519		8		YC063-YD157
	0005	22		GA		27-8	23-32-63	D10319		9		D10519		3		YC051-YC062
I	0005	22		PA		29-6	23-32-63	D10319		9		D10519		3		YC063-YD157
	0007	22		GA		27-8	23-32-63	D10319		4		D10519		5		YC051-YC062
I	0007	22		PA		29-6	23-32-63	D10319		4		D10519		5		YC063-YD157
	0008	22		GA		27-8	23-32-63	D10319		7		D10519		6		YC051-YC062
I	0008	22		PA		29-6	23-32-63	D10319		7		D10519		6		YC063-YD157
	0009	22		GA		27-8	23-32-63	D10319		8		D10519		7		YC051-YC062
I	0009	22		PA		29-6	23-32-63	D10319		8		D10519		7		YC063-YD157
I	001CO			AA		0-0	23-32-63	D10319		=C1		D10521		=C1		YC051-YD157
	001CX			OF	AA	27-2	23-32-63	D10319		=A1	5P	D10521		=A1		YC051-YC062

WIRE LIST

D280A108

91-21-11

Section W3060

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3063	286A3063			PSU MOUNTED LCD VIDEO MONITOR NO.32 TO VDU IN CLUSTER NO.4 (continued)											
001CX		0F	AA		29-0	23-32-63	D10319	= A1	5M		D10521	= A1			YC063-YD157

For training purposes only!

WIRE LIST

D280A108

91-21-11

Section W3060

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W3071	286A3071				VIDEO - VDU CLUSTER 1 TO VDU CLUSTER 2											
0001	20		PA		4-0	23-32-41	D10233		11			D45269J	1			YC051-YD170
0002	20		PA		4-0	23-32-41	D10233		12			D45269J	2			YC051-YD170
0003	20		PA		6-2	23-32-41	D10233		13			GD08012	ST..	1		YC051-YD157
0003	20		PA		6-1	23-32-41	D10233		13			GD08012	ST..	1		YD158-YD170
0004	20		PA		6-1	23-32-41	D10233		19			GD08012	ST..	1		YD158-YD170
2501B	24		OT	AA	20-2	23-32-41	D10233		8			D10211	8			YC051-YD170
2501W	24		OT	AA	0-0	23-32-41	D10233		7			D10211	7			YC051-YD170
2501Z				AA	0-0	23-32-41	D10233		9			D10211	9			YC051-YD170
2502B	24		7P	AB	20-2	23-32-41	D10233		1			D10211	1			YC051-YD170
2502BN	24		7P	AB	0-0	23-32-41	D10233		2			D10211	2			YC051-YD170
2502Z				AB	0-0	23-32-41	D10233		3			D10211	3			YC051-YD170
2503B	24		7P	AC	20-2	23-32-41	D10233		4			D10211	4			YC051-YD170
2503BN	24		7P	AC	0-0	23-32-41	D10233		5			D10211	5			YC051-YD170
2503Z				AC	0-0	23-32-41	D10233		6			D10211	6			YC051-YD170
2504B	24		7P	AD	20-2	23-32-41	D10233		14			D10211	14			YC051-YD170
2504BN	24		7P	AD	0-0	23-32-41	D10233		15			D10211	15			YC051-YD170
2504Z				AD	0-0	23-32-41	D10233		16			D10211	16			YC051-YD170
W3073	286A3073				VIDEO - VDU CLUSTER 3 TO VDU CLUSTER 4											
0001	20		PA		4-0	23-32-61	D10297		11			D45273J	1			YC051-YD170
0002	20		PA		4-0	23-32-61	D10297		12			D45273J	2			YC051-YD170
0003	20		PA		3-7	23-32-61	D10297		13			GD08028	ST..	1		YC051-YD153
0003	20		PA		3-8	23-32-61	D10297		13			GD08028	ST..	1		YD154-YD170
0004	20		PA		3-8	23-32-61	D10297		19			GD08028	ST..	1		YD158-YD170
2501B	24		OT	AA	24-11	23-32-61	D10297		8			D10283	8			YC051-YD153
2501B	24		OT	AA	25-0	23-32-61	D10297		8			D10283	8			YD154-YD157
2501B	24		OT	AA	25-10	23-32-61	D10297		8			D10275	8			YD158-YD170
2501W	24		OT	AA	0-0	23-32-61	D10297		7			D10283	7			YC051-YD157
2501W	24		OT	AA	0-0	23-32-61	D10297		7			D10275	7			YD158-YD170
2501Z				AA	0-0	23-32-61	D10297		9			D10283	9			YC051-YD157
2501Z				AA	0-0	23-32-61	D10297		9			D10275	9			YD158-YD170
2502B	24		7P	AB	24-11	23-32-61	D10297		1			D10283	1			YC051-YD153
2502B	24		7P	AB	25-0	23-32-61	D10297		1			D10283	1			YD154-YD157
2502B	24		7P	AB	25-10	23-32-61	D10297		1			D10275	1			YD158-YD170
2502BN	24		7P	AB	0-0	23-32-61	D10297		2			D10283	2			YC051-YD157
2502BN	24		7P	AB	0-0	23-32-61	D10297		2			D10275	2			YD158-YD170
2502Z				AB	0-0	23-32-61	D10297		3			D10283	3			YC051-YD157
2502Z				AB	0-0	23-32-61	D10297		3			D10275	3			YD158-YD170
2503B	24		7P	AC	24-11	23-32-61	D10297		4			D10283	4			YC051-YD153

WIRE LIST

D280A108

91-21-11

Section W3070

Page 1

Nov 12/2012



Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3073	286A3073			VIDEO - VDU CLUSTER 3 TO VDU CLUSTER 4 (continued)											
2503B	24		7P	AC	25-0	23-32-61	D10297				D10283				YD154-YD157
2503B	24		7P	AC	25-10	23-32-61	D10297				D10275				YD158-YD170
2503BN	24		7P	AC	0-0	23-32-61	D10297				D10283				YC051-YD157
2503BN	24		7P	AC	0-0	23-32-61	D10297				D10275				YD158-YD170
2503Z				AC	0-0	23-32-61	D10297				D10283				YC051-YD157
2503Z				AC	0-0	23-32-61	D10297				D10275				YD158-YD170
2504B	24		7P	AD	24-11	23-32-61	D10297				D10283				YC051-YD153
2504B	24		7P	AD	25-0	23-32-61	D10297				D10283				YD154-YD157
2504B	24		7P	AD	25-10	23-32-61	D10297				D10275				YD158-YD170
2504BN	24		7P	AD	0-0	23-32-61	D10297				D10283				YC051-YD157
2504BN	24		7P	AD	0-0	23-32-61	D10297				D10275				YD158-YD170
2504Z				AD	0-0	23-32-61	D10297				D10283				YC051-YD157
2504Z				AD	0-0	23-32-61	D10297				D10275				YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W3070

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3097	286A3097			DISCONNECT FOR LCD MONITOR 2 TO VDU IN CLUSTER 1											
0001	20	PA		6-7	23-32-33	D10005P		1			D10339		1		YC051-YD157
0002	20	PA		6-7	23-32-33	D10005P		2			D10339		4		YC051-YD157
0003	22	PA		6-7	23-32-33	D10005P		10			D10339		2		YC051-YD157
0004	24	PK		6-7	23-32-33	D10005P		6			D10339		8		YC051-YD157
0005	22	PA		6-7	23-32-33	D10005P		9			D10339		3		YC051-YD157
0007	22	PA		6-7	23-32-33	D10005P		4			D10339		5		YC051-YD157
0008	22	PA		6-7	23-32-33	D10005P		7			D10339		6		YC051-YD157
0009	22	PA		6-7	23-32-33	D10005P		8			D10339		7		YC051-YD157
001CO			AA	0-0	23-32-33	D10007P		=C1			D10339		=C1		YC051-YD157
001CX		0F	AA	6-1	23-32-33	D10007P		=A1			D10339		=A1		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W3090

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To			Effectivity				
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type		Splice	Equip	Term	Type
I	W3101	286A3101	SATCOM- RF COMBINER TO LNA/DIP (PORT)												
I	001CO			AA	0-0	23-15-12	D10875	= C1			D10879	= C1			YC051-YD157
I	001CX		JB	AA	3-0	23-15-12	D10875	= A1			D10879	= A1			YC051-YD157
I	W3103	286A3103	SATCOM- RF UNIT TO RF COMBINER (J3)												
I	001CO			CA	0-0	23-15-12	D10873	= C1			D41617P	= C1			YC051-YD157
I	001CX		OK	CA	24-0	23-15-12	D10873	= A1			D41617P	= A1			YC051-YD157
I	W3105	286A3105	SATCOM- RF COMBINER TO LNA/DIP (PORT)												
I	001CO			MA	0-0	23-15-13	D10877	= C1			D41621P	= C1			YC051-YD157
I	001CX		OF	MA	24-7	23-15-13	D10877	= A1			D41621P	= A1			YC051-YD157
I	W3107	286A3107	SATCOM- AERO-1 ANTENNA												
I	0001	22		PA	28-11	23-15-12	D10863		1		D41619P		1		YC051-YD157
I	0002	22		PA	28-11	23-15-12	D10863		2		D41619P		2		YC051-YD157
I	0003	22		PA	28-11	23-15-12	D10863		3		D41619P		3		YC051-YD157
I	0004	24		PK	25-2	23-15-13	D10861		B		D41619P		4		YC051-YD157
I	0005	20		GK	5-5	23-15-11	D10861		J		GD03764	ST..	1		YC051-YD157
I	0007	24		PK	25-2	23-15-13	D10861		H		D41619P		7		YC051-YD157
I	0010	22		PA	3-11	23-15-12	D10863		10		GD03764	ST..	1		YC051-YD157
I	0011	20		PA	11-4	23-15-11	SM00001			9	D40165P		1		YC051-YC052
I	0011	20		PA	103-11	23-15-11	D41601P		1		D40165P		1		YC053-YD157
I	0012	20		PA	25-2	23-15-11	D10861		F		D41613P		1		YC051-YD157
I	0013	20		PA	5-5	23-15-11	D10861		E		GD03764	AC..	1		YC051-YD157
I	0014	20		PA	5-5	23-15-11	D10861		A		GD03764	ST..	1		YC051-YD157
I	0016	20		PA	11-4	23-15-11	SM00002			9	D40165P		2		YC051-YC052
I	0016	20		PA	103-11	SPARE	D41601P		2		D40165P		2		YC053-YD157
I	0017	20		PA	11-4	23-15-11	SM00003			9	D40165P		3		YC051-YC052
I	0017	20		PA	103-11	SPARE	D41601P		3		D40165P		3		YC053-YD157
I	0051	20		PA	69-6	23-15-11	SM00001			9	SM00004			9	YC051-YC052
I	0056	20		PA	69-6	23-15-11	SM00002			9	SM00005			9	YC051-YC052
I	0057	20		PA	69-6	23-15-11	SM00003			9	SM00006			9	YC051-YC052
I	0111	20		PA	25-1	23-15-11	SM00004			9	D41601P		1		YC051-YC052
I	0116	20		PA	25-1	23-15-11	SM00005			9	D41601P		2		YC051-YC052
I	0117	20		PA	25-1	23-15-11	SM00006			9	D41601P		3		YC051-YC052
I	0201B	22		PB	A	28-11	23-15-12	D10863		6	D41619P		6		YC051-YD157
I	0201R	22		PB	A	0-0	23-15-12	D10863		5	D41619P		5		YC051-YD157
I	2001B	24		Y2	B	28-11	23-15-12	D10863		12	D41619P		12		YC051-YD157
I	2001R	24		Y2	B	0-0	23-15-12	D10863		11	D41619P		11		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W3100

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity

W3107		286A3107			SATCOM- AERO-1 ANTENNA (continued)											
2001Z					B	0-0	23-15-12	D10863		S/R		D41619P		S/R		YC051-YD157
2002B		24		Y2	C	28-11	23-15-12	D10863		9		D41619P		9		YC051-YD157
2002R		24		Y2	C	0-0	23-15-12	D10863		8		D41619P		8		YC051-YD157
2002Z					C	0-0	23-15-12	D10863		S/R		D41619P		S/R		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W3100

Page 2 End

Nov 12/2012



WIRE LIST

91-21-11

Section W3130

Page 1

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3139	286A3139			PSU LCD VIDEO MONITOR (STA 757R TO 817R) TO VDU ON TRAY 4											
0001	20		PA		20-6	23-32-63	D10319		1		D10979		1		YD158-YD170
0002	20		PA		20-6	23-32-63	D10319		2		D10979		4		YD158-YD170
0003	22		PA		20-6	23-32-63	D10319		10		D10979		2		YD158-YD170
0004	24		PK		20-6	23-32-63	D10319		6		D10979		8		YD158-YD170
0005	20		PA		20-2	23-32-63	D10319		9		SM00001			S	YD158-YD170
0006	20		PA		0-10	23-32-63	D10979		3		SM00001			S	YD158-YD170
0007	20		PA		0-10	23-32-63	D10979		5		SM00001			S	YD158-YD170
0008	20		PA		0-10	23-32-63	D10979		6		SM00001			S	YD158-YD170
0009	20		PA		0-10	23-32-63	D10979		7		SM00001			S	YD158-YD170
001CO				AA	0-0	23-32-63	D10319		=C1		D10981		=C1		YD158-YD170
001CX		0F		AA	20-0	23-32-63	D10319		=A1	5M	D10981		=A1		YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W3130

Page 2 End

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3141	286A3141				GLIDE SLOPE ANT LEFT - STA 178 TO E1-2 SHELF										
001CO				AA	0-0	34-31-11	D03317	= C1		D04025J	= C1			ALL	
001CX		OF		AA	14-8	34-31-11	D03317	= A1		D04025J	= A1			ALL	
W3142	286A3142				EMERGENCY EXIT LIGHT - LEFT										
0016	20	PA			10-5	33-51-14	D40100J	5		D12016	1			YC051-YD170	
0031	22	PA			48-5	33-51-11	D40196J	1		SM00007		S		YC051-YD157	
0031	22	PA			48-5	33-51-11	D40196J	1		SM00007		9		YD158-YL999, YR301-YR328	
0031	22	PA			40-2	33-51-11	D40196J	1		SM00007		9		YN231-YN501	
0032	22	PA			48-5	33-51-11	D40196J	2		SM00008		S		YC051-YD157	
0032	22	PA			48-5	33-51-11	D40196J	2		SM00008		9		YD158-YL999, YR301-YR328	
0032	22	PA			40-2	33-51-11	D40196J	2		SM00008		9		YN231-YN501	
0034	18	PA			32-2	33-41-11	D40196J	4	18	L00034	PWR	E		YC051-YD170	
0034	18	PA			32-4	33-41-11	D40196J	4	18	L00034	PWR	E		YL951-YL999, YR301-YR328	
0034	18	PA			24-1	33-41-11	D40196J	4	18	L00034	PWR	E		YN231-YN501	
0035	20	PA			48-5	33-51-11	D40196J	5		SM00005		S		YC051-YD157	
0035	20	PA			48-5	33-51-11	D40196J	5		SM00005		9		YD158-YL999, YR301-YR328	
0035	20	PA			40-2	33-51-11	D40196J	5		SM00005		9		YN231-YN501	
0038	20	PA			90-5	SPARE	D40196J	8		D10746	CAP	Y		YC051-YL999, YR301-YR328	
0038	20	PA			71-2	SPARE	D40196J	8		D10746	CAP	Y		YN231-YN501	
0039	20	PA			90-5	SPARE	D40196J	CAP	Y	D10746	CAP	Y		YC051-YD157, YL951-YL999, YR301-YR328	
0039	20	PA			90-9	SPARE	D40196J	CAP	Y	D10746	CAP	Y		YD158-YD170	
0039	20	PA			71-2	SPARE	D40196J	CAP	Y	D10746	CAP	Y		YN231-YN501	
0041	20	PA			41-7	33-51-11	SM00001		S	SM00002		S		YC051-YD157	
0041	20	PA			41-7	33-51-11	SM00001		9	SM00002		9		YD158-YL999, YR301-YR328	
0041	20	PA			32-7	33-51-11	SM00001		9	SM00002		9		YN231-YN501	
0042	20	PA			39-2	33-51-11	SM00002		S	SM00005		S		YC051-YD157	
0042	20	PA			39-2	33-51-11	SM00002		9	SM00005		9		YD158-YL999, YR301-YR328	
0042	20	PA			36-6	33-51-11	SM00002		9	SM00005		9		YN231-YN501	
0043	22	PA			39-2	33-51-11	SM00003		S	SM00007		S		YC051-YD157	

WIRE LIST

D280A108

91-21-11

Section W3140

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3142	286A3142				EMERGENCY EXIT LIGHT - LEFT (continued)										
0043	22		PA		39-2	33-51-11	SM00003		9		SM00007		9		YD158-YL999, YR301-YR328
0043	22		PA		37-4	33-51-11	SM00003		9		SM00007		9		YN231-YN501
0044	22		PA		39-2	33-51-11	SM00004		S		SM00008		S		YC051-YD157
0044	22		PA		39-2	33-51-11	SM00004		9		SM00008		9		YD158-YL999, YR301-YR328
0044	22		PA		37-4	33-51-11	SM00004		9		SM00008		9		YN231-YN501
0051	20		PA		1-0	33-51-21	D12052		1		SM00023		9		YD158-YR328
0056	20		PA		3-0	33-51-14	D12016		2		GD03770	DC..	1		YC051-YD170
0057	20		PA		6-10	33-51-13	D40098J		6		D12028		1		YC051-YL999
0057	20		PA		14-1	33-51-12	D40096P		3		SM00106		9		YN501
0057	20		PA		10-3	33-51-13	D40098J		6		D15242		1		YR301-YR328
0058	20		PA		5-3	33-51-13	D12028		2		GD03728	DC..	1		YC051-YD157
0058	20		PA		5-3	33-51-13	GD03728		DC..	1	D12028		2		YD158-YL999
0058	20		PA		6-10	33-51-13	GD03728		DC..	1	D15242		2		YR301-YR328
0059	16		PA		1-0	33-51-14	SM00022		9		D11080		1		YC051-YL999, YR301-YR328
0060	16		PA		11-4	33-51-14	D11080		2		GD08038	DC..	1		YC051-YL999, YR301-YR328
0061	18		PA		4-1	33-41-11	L00034	RTN	E		GD07004	AC..	1		YC051-YD170
0061	18		PA		6-4	33-41-11	L00034	RTN	E		GD07004	AC..	1		YL951-YL999, YR301-YR328
0061	18		PA		3-0	33-41-11	L00034	RTN	E		GD03874	AC..	1		YN231-YN501
0062	18		PA		4-1	33-41-11	L00034	CASE	E		GD07004	ST..	1		YC051-YD170
0062	18		PA		6-4	33-41-11	L00034	CASE	E		GD07004	ST..	1		YL951-YL999, YR301-YR328
0062	18		PA		2-9	33-41-11	L00034	CASE	E		GD03874	ST..	1		YN231-YN501
0063	16		PA		22-6	33-51-12	D40086P		6		D12046		1		YC051-YD157
0064	16		PA		6-8	33-51-12	D12046		2		GD08012	DC..	1		YC051-YL999
0065	20		PA		8-2	33-51-12	D40086P		5		D12048		1		YC051-YD157
0066	20		PA		7-0	33-51-12	D12048		2		GD03866	DC..	1		YC051-YL999
0066	20		PA		4-1	33-51-12	D14828		B		GD08010	DC..	1		YR301-YR328
0067	20		PA		15-8	33-51-12	D40086P		2		D12062		1		YC051-YD157
0068	20		PA		7-1	33-51-12	D12062		2		GD08010	DC..	1		YC051-YL999
0068	16		PA		6-5	33-51-12	D14694		B		GD03866	DC..	1		YR301-YR328
0072	16		PA		12-7	33-51-21	SM00058		S		D03670	=1	VY		YC051-YD157
0072	20		PA		16-8	33-51-21	D40098J		3		D03670	=1	VY		YD158-YL999, YR301-YR328
0073	16		PA		8-9	33-51-21	D03672		=1	VG	GD03744	DC..	1		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W3140

Page 2

Nov 12/2012

Bundle No.	Part Number			Description	From			To							
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3142	286A3142			EMERGENCY EXIT LIGHT - LEFT (continued)											
0073	20		PA		8-9	33-51-21	D03672	= 1	VG		GD03744	DC..	1		YD158-YL999, YR301-YR328
0074	20		PA		19-0	33-51-22	D10130	2			SP00642		S		YC051-YD157
0075	20		PA		1-8	33-51-22	D10130	5			GD11730	DC..	1		YC051-YD157
0077	20		PA		1-0	33-51-21	D12052	2			SM00023		9		YL951-YL999, YN501-YR328
0078	20		PA		3-0	33-51-21	D12052	4			GD03780	DC..	1		YD158-YL999, YR301-YR328
0078	20		PA		2-10	33-51-21	D12052	4			GD03780	DC..	1		YN231-YN501
0079	16		PA		3-0	33-51-21	D12052	5	16		GD03780	DC..	1		YD158-YL999, YR301-YR328
0079	20		PA		2-10	33-51-21	D12052	5			GD03780	DC..	1		YN231-YN260
0079	16		PA		2-10	33-51-21	D12052	5	16		GD03780	DC..	1		YN501
0080	16		PA		19-7	33-51-21	SM00018		S		D40098J		8		YC051-YD157
0080	20		PA		21-2	33-51-21	SM00018		9		D40098J		8		YD158-YL999, YR301-YR328
0081	16		PA		27-11	33-51-21	D12434	= 1	VY		SM00016		S		YC051-YD157
0082	16		PA		4-3	33-51-21	D12436	= 1	VG		GD03754	DC..	1		YC051-YD157
0082	20		PA		4-3	33-51-22	D12436	= 1	VG		GD03754	DC..	1		YD158-YL999, YR301-YR328
0083	20		PA		36-7	33-51-21	D40086P	1			D10138		2		YC051-YD157
0084	16		PA		3-7	33-51-21	SM00016		S		D12068	= 1	VY		YC051-YD157
0085	16		PA		25-11	33-51-21	D10138	1	16		SM00058		S		YC051-YD157
0086	16		PA		10-2	33-51-21	D40096P	6	16		SM00015		9		YD158-YD170
0086	16		PA		8-4	33-51-21	D40096P	6	16		SM00015		9		YN231-YN260
0091	20		PA		32-3	33-51-22	D40100J	4			D10132		1		YC051-YD157
0091	16		PA		21-3	33-51-22	D40100J	4			SM00070		9		YD158-YL999
0091	16		PA		21-4	33-51-22	D10746	12	16		SM00070		9		YR301-YR328
0098	20		PA		47-7	52-71-14	D40096P	8			D46440P		1		YC051-YL999, YR301-YR328
0098	20		PA		38-2	52-71-14	D40096P	8			D46440P		1		YN231-YN501
0111	18		PA		15-11	33-51-12	D11074	1			D40096P		1	18	YC051-YD157, YN231-YN501
0111	16		PA		15-11	33-51-12	D11074	1			D40096P		1	16	YD158-YL999, YR301-YR328
0115	20		PA		9-1	33-51-12	D11088	1			D40096P		2		YC051-YD170
0116	20		PA		17-5	33-51-12	D11090	1			D40096P		3		YN231-YN260
0151	18		PA		2-0	33-51-12	D11074	2			GD03876	DC..	1		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W3140

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3142	286A3142				EMERGENCY EXIT LIGHT - LEFT (continued)										
0151	16		PA		2-0	33-51-12	D11074	2			GD03876	DC..	1		YD158-YL999, YR301-YR328
0151	18		PA		2-2	33-51-12	D11074	2			GD03876	DC..	1		YN231-YN501
0155	20		PA		4-10	33-51-12	D11088	2			GD03852	DC..	1		YC051-YD170
0156	20		PA		4-5	33-51-12	D11090	2			GD03860	DC..	1		YN231-YN260
0190	16		PA		22-3	33-51-21	D40096P	4	16		SM00023		9		YD158-YD170
0190	16		PA		22-2	33-51-21	D40096P	4	16		SM00023		9		YL951-YL999, YR301-YR328
0190	16		PA		21-9	33-51-21	D40096P	4	16		SM00023		9		YN231-YN501
0196	16		PA		18-2	33-51-21	SM00015		9		SM00078		9		YD158-YD170
0196	16		PA		15-11	33-51-21	SM00015		9		SM00078		9		YN231-YN260
0197	20		PA		1-0	33-51-21	D12052	2			SM00078		9		YD158-YD170, YN231-YN260
0201	16		PA		2-0	33-51-11	D12008	1	16		GD08000	DC..	1		YC051-YL999, YR301-YR328
0201	16		PA		3-0	33-51-11	D10712	1	16		GD03944	DC..	1		YN231-YN260
0201	16		PA		3-6	33-51-11	D10712	1	16		GD03944	DC..	1		YN501
0202	20		PA		1-0	33-51-11	D12008	2			SM00005		S		YC051-YD157
0202	20		PA		1-0	33-51-11	D12008	2			SM00005		9		YD158-YL999, YR301-YR328
0202	20		PA		1-0	33-51-11	D10712	2			SM00005		9		YN231-YN501
0203	22		PA		1-0	33-51-11	D12008	3			SM00007		S		YC051-YD157
0203	22		PA		1-0	33-51-11	D12008	3			SM00007		9		YD158-YL999, YR301-YR328
0203	22		PA		1-0	33-51-11	D10712	3			SM00007		9		YN231-YN501
0204	22		PA		1-0	33-51-11	D12008	4			SM00008		S		YC051-YD157
0204	22		PA		1-0	33-51-11	D12008	4			SM00008		9		YD158-YL999, YR301-YR328
0204	22		PA		1-0	33-51-11	D10712	4			SM00008		9		YN231-YN501
0206	20		PA		0-7	33-51-11	D12008	5			D12008		6		YC051-YL999, YR301-YR328
0206	20		PA		0-7	33-51-11	D10712	5			D10712		6		YN231-YN501
0207	20		PA		1-11	33-51-11	D12008	7			GD08000	ST..	1		YC051-YL999, YR301-YR328
0207	20		PA		2-3	33-51-11	D10712	7			GD03944	ST..	1		YN231-YN501
0209	20		PA		22-9	33-51-13	D12008	9			D12032		1		YC051-YD157
0209	20		PA		1-0	33-51-13	D10712	9			SM00209		9		YN231-YN260
0209	16		PA		17-0	33-51-13	D10712	9	16		SM00006		9		YN501
0210	20		PA		10-9	33-51-13	D12008	10			D12034		1		YD158-YL999

WIRE LIST

D280A108

91-21-11
Section W3140
Page 4
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3142		286A3142			EMERGENCY EXIT LIGHT - LEFT (continued)											
0210		20		PA		2-3	33-51-21	D10712	12			SM00080		9		YN231-YN260
0210		20		PA		2-3	33-51-21	D10712	12			SM00068		9		YN501
0211		16		PA		1-0	33-51-21	D12008	11	16		SM00018		S		YC051-YD157
0211		20		PA		2-9	33-51-21	D12008	12			SM00018		9		YD158-YL999
0211		20		PA		1-0	33-51-13	D10712	11			SM00211		9		YN231-YN260
0211		16		PA		23-7	33-51-13	D10712	11	16		D11078		1		YN501
0211		20		PA		4-1	33-51-21	D12008	11			D12068	= 1	VY		YR301-YR328
0212		16		PA		1-0	33-51-21	D12008	12	16		SM00016		S		YC051-YD157
0212		20		PA		4-1	33-51-21	D12008	11			D12068	= 1	VY		YD158-YL999
0212		20		PA		4-0	33-51-21	D10712	10			D03670	= 1	VY		YN231-YN260
0212		20		PA		4-0	33-51-21	D10712	13			D03670	= 1	VY		YN501
0212		20		PA		2-9	33-51-21	D12008	12			SM00018		9		YR301-YR328
0213		16		PA		18-1	33-51-13	D12008	13	16		D12442	= 1	VY		YC051-YD157
0213		20		PA		1-0	33-51-13	D12008	13			SM00213		9		YD158-YL999, YR301-YR328
0213		18		PA		16-2	33-51-13	D10712	13	18		D12030		1		YN231-YN260
0213		18		PA		15-1	33-51-13	D10712	14	18		D15242		1		YN501
0214		16		PA		18-5	33-51-13	D12008	14	16		D12446		1		YC051-YD157
0214		20		PA		1-0	33-51-13	D12008	14			SM00214		9		YD158-YL999
0215		16		PA		21-4	33-51-13	D12008	15	16		D12448	= 1	VY		YC051-YD157
0215		20		PA		1-0	33-51-13	D12008	15			SM00215		9		YD158-YL999, YR301-YR328
0215		20		PA		25-11	33-51-21	D10712	15			D12396	= 1	VY		YN231-YN260
0216		16		PA		21-8	33-51-13	D12008	16	16		D12452		1		YC051-YD157
0216		20		PA		1-0	33-51-13	D12008	16			SM00216		9		YD158-YL999
0222		20		PA		1-0	33-51-11	D12008	22			SM00005		S		YC051-YD157
0222		20		PA		1-0	33-51-11	D12008	22			SM00005		9		YD158-YL999, YR301-YR328
0222		20		PA		1-0	33-51-11	D10712	22			SM00005		9		YN231-YN501
0224		20		PA		0-7	33-51-11	D12008	20			D12008		24		YC051-YL999, YR301-YR328
0224		20		PA		0-7	33-51-11	D10712	20			D10712		24		YN231-YN501
0225		16		PA		2-3	33-51-21	D12828	1			SM00018		S		YC051-YD157
0225		20		PA		1-0	33-51-21	SM00018		9		D12828		1		YD158-YD170, YR301-YR328
0225		20		PA		0-7	33-51-21	SM00018		9		D12828		1		YL951-YL999
0226		16		PA		3-0	33-51-21	D12828	2			GD08000	DC..	1		YC051-YD157
0226		20		PA		1-0	33-51-21	D12828	2			SM00018		9		YD158-YD170, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3140

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3142	286A3142				EMERGENCY EXIT LIGHT - LEFT (continued)										
0226	20		PA		0-7	33-51-21	D12828		2		SM00018			9	YL951-YL999
0227	20		PA		3-0	33-51-21	D12828		4		GD08000	DC..	1		YD158-YL999, YR301-YR328
0228	20		PA		3-0	33-51-21	D12828		5		GD08000	DC..	1		YD158-YL999, YR301-YR328
0232	12		PA		34-11	33-51-14	SP00544			S	SM00022			9	YC051-YL999, YR301-YR328
0233	16		PA		17-8	33-51-13	D12442	= 1	VY		SM00213			9	YD158-YL999, YR301-YR328
0234	16		PA		8-5	33-51-21	D40098J		3		SM00058			S	YC051-YD157
0235	16		PA		2-3	33-51-21	D12828		3		SM00018			S	YC051-YD157
0236	16		PA		21-2	33-51-13	D12452		1		SM00216			9	YD158-YL999
0236	20		PA		21-8	33-51-13	D14726		A		D12008		16		YR301-YR328
0237	16		PA		17-11	33-51-13	D12446		1		SM00214			9	YD158-YL999
0237	20		PA		18-5	33-51-13	D14842		A		D12008		14		YR301-YR328
0238	16		PA		20-11	33-51-13	D12448	= 1	VY		SM00215			9	YD158-YL999, YR301-YR328
0245	16		PA		17-8	33-51-22	SP00642			S	SM00092			9	YD158-YD170
0245	16		PA		17-9	33-51-22	SP00642			S	SM00092			9	YL951-YL999
0251	16		PA		2-4	33-51-13	D12036		2		GD03754	DC..	1		YC051-YL999, YR301-YR328
0251	16		PA		3-0	33-51-13	D11078		2		GD03754	DC..	1		YN231-YN501
0252	16		PA		3-11	33-51-21	D12072	= 1	VG		GD08000	DC..	1		YC051-YD157
0252	20		PA		3-11	33-51-21	D12072	= 1	VG		GD08000	DC..	1		YD158-YL999, YR301-YR328
0252	20		PA		4-2	33-51-21	D03672	= 1	VG		GD03944	DC..	1		YN231-YN501
0253	16		PA		11-10	33-51-13	D12452		2		GD03744	DC..	1		YC051-YL999
0253	18		PA		4-6	33-51-13	D12030		2		GD03732	DC..	1		YN231-YN260
0253	18		PA		6-11	33-51-13	D15242		2		GD03732	DC..	1		YN501
0253	20		PA		11-10	33-51-13	D14726		B		GD03744	DC..	1		YR301-YR328
0255	16		PA		11-6	33-51-13	D12450	= 1	VG		GD03744	DC..	1		YC051-YL999, YR301-YR328
0256	20		PA		9-3	33-51-13	D12038		2		GD03754	DC..	1		YC051-YL999
0256	20		PA		5-0	33-51-12	D11096		2		GD03870	DC..	1		YN231-YN260
0259	16		PA		23-6	33-51-13	D11078		1		SM00211			9	YN231-YN260
0260	16		PA		6-2	33-51-13	D12034		2		GD03728	DC..	1		YC051-YD157
0260	20		PA		6-2	33-51-13	D12034		2		GD03728	DC..	1		YD158-YL999
0262	16		PA		3-4	33-51-13	D12448	= 1	VY		SM00006			9	YN231-YN501
0263	16		PA		3-8	33-51-13	D12452		1		SM00006			9	YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W3140

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3142		286A3142			EMERGENCY EXIT LIGHT - LEFT (continued)											
0264		16		PA		3-6	33-51-13	D12452	2			GD03988	DC..	1		YN231-YN260
0265		20		PA		4-7	33-51-21	D12398	=1	VG		GD03754	DC..	1		YN231-YN260
0265		20		PA		4-7	33-51-22	D12398	=1	VG		GD03754	DC..	1		YN501
0269		20		PA		7-3	33-51-13	D12032	2			GD03744	DC..	1		YC051-YD157
0269		16		PA		7-3	33-51-12	D12032	2			GD03744	DC..	1		YD158-YL999, YR301-YR328
0269		16		PA		3-3	33-51-13	D12450	=1	VG		GD03988	DC..	1		YN231-YN501
0270		20		PA		1-7	33-51-21	D10138	5			GD00088	DC..	1		YC051-YD157
0271		16		PA		1-7	33-51-21	D10138	4	16		GD00088	DC..	1		YC051-YD157
0272		16		PA		16-6	33-51-13	SM00209		9		SM00006		9		YN231-YN260
0273		16		PA		7-4	33-51-13	D12446	2			GD03728	DC..	1		YC051-YL999
0273		20		PA		7-4	33-51-13	D14842	B			GD03728	DC..	1		YR301-YR328
0274		16		PA		7-1	33-51-13	D12444	=1	VG		GD03728	DC..	1		YC051-YL999, YR301-YR328
0275		20		PA		11-7	33-51-21	D40096P	6			D12350		1		YC051-YD157
0275		20		PA		1-11	33-51-21	SM00015		9		D12350		1		YD158-YL999
0275		20		PA		4-2	33-51-21	D12350	1			SM00015		9		YN231-YN260
0275		20		PA		11-5	33-51-21	D12350	1			D40096P		6		YN501
0275		20		PA		1-11	33-51-21	D12350	1			SM00015		9		YR301-YR328
0276		20		PA		7-4	33-51-21	D12350	2			GD03734	DC..	1A		YC051-YL999, YR301-YR328
0276		20		PA		7-5	33-51-21	D12350	2			GD03734	DC..	1A		YN231-YN501
0284		20		PA		10-2	33-51-21	SM00015		9		D40096P		6		YL951-YL999
0284		20		PA		10-2	33-51-21	D40096P	6			SM00015		9		YR301-YR328
0295		20		PA		2-4	33-51-21	D13262	5			GD03944	DC..	1		YN231-YN501
0296		20		PA		0-7	33-51-21	D13262	1			SM00080		9		YN231-YN260
0296		20		PA		0-7	33-51-21	D13262	1			SM00068		9		YN501
0297		20		PA		0-7	33-51-21	D13262	2			SM00080		9		YN231-YN260
0297		20		PA		0-7	33-51-21	D13262	2			SM00068		9		YN501
0298		20		PA		2-4	33-51-21	D13262	4			GD03944	DC..	1		YN231-YN501
0301		16		PA		3-0	33-51-11	D10716	1	16		GD03946	DC..	1		YC051-YN260, YR301-YR328
0301		16		PA		3-6	33-51-11	D10716	1	16		GD03946	DC..	1		YN501
0302		20		PA		0-11	33-51-11	D10716	2			SM00002		S		YC051-YD157
0302		20		PA		0-11	33-51-11	D10716	2			SM00002		9		YD158-YL999, YR301-YR328
0302		20		PA		1-0	33-51-11	D10716	2			SM00002		9		YN231-YN501
0303		22		PA		0-11	33-51-11	D10716	3			SM00003		S		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W3140

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3142	286A3142				EMERGENCY EXIT LIGHT - LEFT (continued)										
0303	22		PA		0-11	33-51-11	D10716	3			SM00003		9		YD158-YL999, YR301-YR328
0303	22		PA		21-1	33-51-11	D10716	3			SM00003		9		YN231-YN501
0304	22		PA		0-11	33-51-11	D10716	4			SM00004		S		YC051-YD157
0304	22		PA		0-11	33-51-11	D10716	4			SM00004		9		YD158-YL999, YR301-YR328
0304	22		PA		21-1	33-51-11	D10716	4			SM00004		9		YN231-YN501
0306	20		PA		0-7	33-51-11	D10716	5			D10716	6			ALL
0307	20		PA		2-7	33-51-11	D10716	7			GD03946	ST..	1		YC051-YL999, YR301-YR328
0307	20		PA		2-11	33-51-11	D10716	7			GD03946	ST..	1		YN231-YN501
0308	20		PA		34-10	33-51-22	D12434	= 1	VY		SM00310		9		YD158-YD170
0308	20		PA		35-3	33-51-22	D12434	= 1	VY		D10716	10			YL951-YL999
0308	20		PA		35-3	33-51-22	D10716	10			D12434	= 1	VY		YR301-YR328
0309	16		PA		33-4	33-51-13	D10716	9	16		D12036	1			YC051-YL999, YR301-YR328
0309	20		PA		25-4	33-51-22	D10716	9			D46440P	3			YN501
0310	20		PA		31-6	33-51-22	D10716	10			D10130	1			YC051-YD157
0310	20		PA		1-0	33-51-22	D10716	12			SM00310		9		YD158-YD170
0310	20		PA		3-0	33-51-22	D10716	12			D13258	1			YL951-YL999
0310	20		PA		3-2	33-51-22	D10716	12			SM00074		9		YN231-YN501
0310	20		PA		0-11	33-51-22	D10716	12			SM00074		9		YR301-YR328
0311	20		PA		26-1	33-51-13	D10716	11			D12038	1			YC051-YL999
0311	16		PA		1-0	33-51-13	D10716	11	16		SM00009		9		YN231-YN501
0311	16		PA		1-0	33-51-13	D10716	13	16		SM00011		9		YR301-YR328
0312	16		PA		1-0	33-51-13	D10716	12	16		SM00009		9		YC051-YD157
0312	20		PA		0-11	33-51-13	D10716	10			SM00009		9		YD158-YD170
0312	20		PA		36-1	33-51-22	D12396	= 1	VY		D10716	10			YN501
0313	16		PA		1-0	33-51-13	D10716	13	16		SM00011		9		YC051-YN501
0315	20		PA		18-7	33-51-13	D10716	15			D11100	1			YC051-YL999
0315	20		PA		20-7	33-51-13	D10716	15			D11330	1			YN231-YN260
0315	20		PA		11-9	33-51-13	D10716	15			SM00081		9		YR301-YR328
0316	20		PA		10-2	33-51-13	D10716	16			D11326	1			YC051-YL999
0316	20		PA		14-0	33-51-13	D10716	16			D11334	1			YN231-YN260
0316	20		PA		16-2	33-51-13	D10716	11			D14834	A			YR301-YR328
0322	20		PA		0-11	33-51-11	D10716	22			SM00002		S		YC051-YD157
0322	20		PA		0-11	33-51-11	D10716	22			SM00002		9		YD158-YL999, YR301-YR328
0322	20		PA		1-0	33-51-11	D10716	22			SM00002		9		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3140

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description		From				To					
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3142	286A3142			EMERGENCY EXIT LIGHT - LEFT (continued)											
0324	20		PA		0-7	33-51-11	D10716	20			D10716	24			ALL
0327	14		PA		17-3	33-51-13	SM00009		9		SM00010		9		YC051-YD157
0327	14		PA		38-9	33-51-13	SM00010		9		SM00009		9		YN231-YN501
0328	14		PA		37-9	33-51-13	SM00011		9		SM00012		9		YC051-YL999, YR301-YR328
0328	14		PA		28-4	33-51-13	SM00012		9		SM00011		9		YN231-YN501
0329	16		PA		1-0	33-51-13	D10502	1			SM00010		9		YC051-YD157
0329	16		PA		17-10	33-51-13	D10502	1			SM00009		9		YD158-YD170
0329	16		PA		1-0	33-51-13	SM00010		9		D11080	1			YN231-YN501
0331	16		PA		1-0	33-51-13	D11082	1			SM00012		9		YC051-YL999, YR301-YR328
0331	16		PA		1-0	33-51-13	SM00012		9		D11082	1			YN231-YN501
0341	14		PA		14-7	33-51-13	SP00546		S		SM00046		9		YC051-YD157
0342	16		PA		1-1	33-51-13	SM00046		9		D12034	1			YC051-YD157
0350	20		PA		1-8	33-51-22	D10130	4			GD11730	DC..	1		YC051-YD157
0351	16		PA		3-2	33-51-13	D11080	2			GD03762	DC..	1		YN231-YN501
0353	16		PA		8-1	33-51-13	D11082	2			GD08038	DC..	1		YC051-YL999, YR301-YR328
0353	16		PA		1-10	33-51-13	D11082	2			GD03758	DC..	1		YN231-YN501
0355	20		PA		4-0	33-51-13	D11100	2			GD03848	DC..	1		YC051-YL999
0355	20		PA		3-11	33-51-12	D11100	2			GD03742	DC..	1		YN231-YN260
0356	20		PA		3-1	33-51-13	D11326	2			GD03756	DC..	1		YC051-YL999
0356	20		PA		4-9	33-51-12	D11326	2			GD03744	DC..	1		YN231-YN260
0356	20		PA		3-2	33-51-13	D14834	B			GD08020	DC..	1		YR301-YR328
0362	16		PA		4-11	33-51-13	D10502	2			GD03848	DC..	1		YC051-YD170
0375	20		PA		13-11	33-51-21	D12748	1			SM00015		9		YL951-YL999, YR301-YR328
0376	20		PA		14-8	33-51-21	D12748	2			GD03734	DC..	1A		YL951-YL999, YR301-YR328
0391	20		PA		1-0	33-51-22	D13258	1			SM00074		9		YN231-YN260
0391	20		PA		0-7	33-51-22	D13258	1			SM00074		9		YN501
0391	20		PA		2-7	33-51-22	D13258	1			SM00074		9		YR301-YR328
0392	20		PA		1-0	33-51-22	D13258	2			SM00092		9		YD158-YL999
0392	20		PA		1-0	33-51-22	D13258	2			SM00074		9		YN231-YN260
0392	20		PA		0-7	33-51-22	D13258	2			SM00074		9		YN501
0392	20		PA		2-7	33-51-22	D13258	2			SM00074		9		YR301-YR328
0393	20		PA		2-7	33-51-22	SM00310		9		D13258	1			YD158-YD170
0394	20		PA		3-9	33-51-22	D13258	4			GD03946	DC..	1		YD158-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3140

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3142	286A3142				EMERGENCY EXIT LIGHT - LEFT (continued)										
0394	20		PA		3-10	33-51-22	D13258	4			GD03946	DC..	1		YN231-YN501
0395	16		PA		3-9	33-51-22	D13258	5	16		GD03946	DC..	1		YD158-YL999, YR301-YR328
0395	20		PA		3-10	33-51-22	D13258	5			GD03946	DC..	1		YN231-YN501
0401	16		PA		3-5	33-51-11	D10746	1	16		GD03948	DC..	1		YC051-YN260, YR301-YR328
0401	16		PA		3-6	33-51-11	D10746	1	16		GD03948	DC..	1		YN501
0402	20		PA		1-2	33-51-11	D10746	2			SM00001		S		YC051-YD157
0402	20		PA		1-2	33-51-11	D10746	2			SM00001		9		YD158-YL999, YR301-YR328
0402	20		PA		1-1	33-51-11	D10746	2			SM00001		9		YN231-YN501
0403	22		PA		42-2	33-51-11	D10746	3			SM00003		S		YC051-YD157
0403	22		PA		42-2	33-51-11	D10746	3			SM00003		9		YD158-YL999, YR301-YR328
0403	22		PA		13-7	33-51-11	D10746	3			SM00003		9		YN231-YN501
0404	22		PA		42-2	33-51-11	D10746	4			SM00004		S		YC051-YD157
0404	22		PA		42-2	33-51-11	D10746	4			SM00004		9		YD158-YL999, YR301-YR328
0404	22		PA		13-7	33-51-11	D10746	4			SM00004		9		YN231-YN501
0405	20		PA		45-5	52-71-14	D46438P	1			D40096P	12			YC051-YL999, YR301-YR328
0406	20		PA		0-7	33-51-11	D10746	5			D10746	6			ALL
0407	20		PA		3-5	33-51-11	D10746	7			GD03948	ST..	1		YC051-YL999, YR301-YR328
0407	20		PA		3-7	33-51-11	D10746	7			GD03948	ST..	1		YN231-YN501
0409	20		PA		8-2	33-51-14	D10746	9			D40044P	3			YC051-YL999, YR301-YR328
0409	20		PA		3-6	33-51-14	D10746	9			D40100J	2			YN231-YN501
0410	20		PA		32-5	33-51-22	D10746	10			D10132	2			YC051-YC060
0410	20		PA		32-5	33-51-22	D10746	14			D10132	2			YC061-YD157
0410	16		PA		21-4	33-51-22	D10746	12	16		SM00090		9		YD158-YD170
0410	20		PA		15-0	33-51-22	D10746	10			D10082	= 1			YL951-YL999
0410	16		PA		21-4	33-51-22	D10746	12	16		SM00070		9		YN231-YN501
0411	18		PA		14-9	33-51-14	D10746	11	18		D11086	1			YC051-YD157
0411	20		PA		1-0	33-51-14	D10746	11			SM00411		9		YD158-YL999, YR301-YR328
0411	18		PA		13-11	33-51-14	D10746	11	18		D11086	1			YN231-YN501
0412	20		PA		5-0	33-51-22	D10746	12			SP00412		S		YC051-YD157

WIRE LIST

D280A108

91-21-11
Section W3140
Page 10
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To							
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3142	286A3142			EMERGENCY EXIT LIGHT - LEFT (continued)											
0412	20		PA		15-0	33-51-22	D10746	10			D10082	= 1	VY		YD158-YD170, YR301-YR328
0412	16		PA		21-4	33-51-22	D10746	12	16		SM00090		9		YL951-YL999
0412	20		PA		4-11	33-51-22	D10746	13			SP00412		S		YN231-YN501
0413	20		PA		5-0	33-51-14	D10746	13			SP03484		S		YC051-YL999, YR301-YR328
0414	20		PA		5-0	33-51-22	D10746	14			SP00412		S		YD158-YL999, YR301-YR328
0415	20		PA		27-5	33-51-14	D10746	15			D11334	1			YC051-YL999
0416	20		PA		20-7	33-51-14	D10746	16			D11338	1			YC051-YL999
0416	20		PA		20-0	33-51-14	D10746	16			D11338	1			YN231-YN260
0416	20		PA		9-0	33-51-14	D10746	16			SM00083		9		YR301-YR328
0418	20		PA		12-11	52-71-13	SM00056		9		SP00802		9		YC051-YL999, YR301-YR328
0419	20		PA		9-10	52-71-13	SP00818		9		SM00056		9		YC051-YL999, YR301-YR328
0420	20		PA		49-0	52-71-13	SP00820		9		D40196J	22			YC051-YL999, YR301-YR328
0422	20		PA		1-2	33-51-11	D10746	22			SM00001		S		YC051-YD157
0422	20		PA		1-2	33-51-11	D10746	22			SM00001		9		YD158-YL999, YR301-YR328
0422	20		PA		1-1	33-51-11	D10746	22			SM00001		9		YN231-YN501
0424	20		PA		0-7	33-51-11	D10746	20			D10746	24			ALL
0434	20		PA		50-7	52-71-13	SP00822		9		D40096P	9			YC051-YL999, YR301-YR328
0435	20		PA		9-11	52-71-13	SP00824		9		GD03728	DC..	1		YC051-YL999, YR301-YR328
0436	20		PA		50-5	52-71-13	D40096P	10			SP00826		9		YC051-YL999, YR301-YR328
0437	20		PA		9-3	52-71-13	SP00828		9		GD08000	DC..	1		YC051-YL999, YR301-YR328
0438	20		PA		10-11	52-71-13	D46438P	2			SP00830		9		YC051-YL999, YR301-YR328
0439	20		PA		11-8	52-71-13	SP00832		9		GD03728	DC..	1		YC051-YL999, YR301-YR328
0440	20		PA		8-5	33-51-14	D14720	A			SM00083		9		YR301-YR328
0441	20		PA		11-4	33-51-14	D14838	A			SM00083		9		YR301-YR328
0442	20		PA		15-9	33-51-22	SP00412		S		D10082	= 1	VY		YC051-YD157
0442	20		PA		15-10	33-51-22	D10082	= 1	VY		SP00412		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3140

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3142	286A3142				EMERGENCY EXIT LIGHT - LEFT (continued)										
0444	16		PA		14-1	33-51-14	D11086		1		SM00411		9		YD158-YL999, YR301-YR328
0448	20		PA		19-4	33-51-14	D14718		A		D10746		15		YN501
0448	16		PA		3-0	33-51-14	D14838		B		GD03764	DC..	1		YR301-YR328
0449	16		PA		2-6	33-51-14	D14718		B		GD03764	DC..	1		YN501
0450	20		PA		2-4	33-51-22	D10132		5		GD08036	DC..	1		YC051-YD157
0451	18		PA		3-2	33-51-14	D11086		2		GD03778	DC..	1		YC051-YL999, YR301-YR328
0451	18		PA		2-11	33-51-14	D11086		2		GD03778	DC..	1		YN231-YN501
0452	20		PA		3-6	33-51-22	D10084		=1	VG	GD03778	DC..	1		YC051-YL999, YR301-YR328
0452	20		PA		3-8	33-51-22	D10084		=1	VG	GD03778	DC..	1		YN231-YN501
0454	20		PA		4-4	33-51-13	D11330		2		GD04004	DC..	1		YN231-YN260
0455	20		PA		2-11	33-51-14	D11334		2		GD08024	DC..	1		YC051-YL999
0455	20		PA		4-8	33-51-13	D11334		2		GD03756	DC..	1		YN231-YN260
0456	20		PA		3-1	33-51-14	D11338		2		GD03764	DC..	1		YC051-YL999
0456	20		PA		4-2	33-51-14	D11338		2		GD03764	DC..	1		YN231-YN260
0456	20		PA		9-5	33-51-14	D14720		B		GD03764	DC..	1		YR301-YR328
0460	20		PA		17-3	52-71-13	D46440P		2		SP00814		9		YC051-YL999, YR301-YR328
0460	20		PA		12-11	52-71-13	D46440P		2		SP00814		9		YN231-YN501
0461	20		PA		8-2	52-71-13	SP00816		9		GD03754	DC..	1		YC051-YL999, YR301-YR328
0461	20		PA		8-5	52-71-13	SP00816		9		GD03754	DC..	1		YN231-YN501
0462	20		PA		40-2	52-71-13	D40196J		17		SM00056		9		YC051-YL999, YR301-YR328
0462	20		PA		42-10	52-71-13	D40196J		17		SP00802		9		YN231-YN501
0463	20		PA		52-6	52-71-13	D40196J		18		SP00804		9		YC051-YL999, YR301-YR328
0463	20		PA		42-10	52-71-13	D40196J		18		SP00804		9		YN231-YN501
0464	20		PA		54-3	52-71-13	D40096P		5		SP00806		9		YC051-YL999, YR301-YR328
0464	20		PA		45-4	52-71-13	D40096P		5		SP00806		9		YN231-YN501
0465	20		PA		6-11	52-71-13	SP00808		9		GD03988	DC..	1		YC051-YL999, YR301-YR328
0465	20		PA		6-10	52-71-13	SP00808		9		GD03988	DC..	1		YN231-YN501
0466	20		PA		52-10	52-71-13	D40096P		7		SP00810		9		YC051-YL999, YR301-YR328
0466	20		PA		41-7	52-71-13	D40096P		7		SP00810		9		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3140

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Diagram	From	To							
Wire No.	GA	CO TY	Fam			FT-IN	Equip	Term	Type	Splice	Equip	Term	Type	Splice
W3142	286A3142			EMERGENCY EXIT LIGHT - LEFT (continued)										
0467	20	PA		7-2	52-71-13	SP00812		9		GD03744	DC..	1		YC051-YL999, YR301-YR328
0467	20	PA		9-11	52-71-13	SP00812		9		GD03944	DC..	1		YN231-YN501
0468	20	PA		2-5	33-51-22	D13124		5		GD03372	DC..	1		YD158-YL999, YR301-YR328
0468	20	PA		2-8	33-51-22	D13124		5		GD03372	DC..	1		YN231-YN260
0468	16	PA		2-8	33-51-22	D13124		5	16	GD03372	DC..	1		YN501
0469	16	PA		2-5	33-51-22	D13124		4	16	GD03372	DC..	1		YD158-YL999, YR301-YR328
0469	20	PA		2-8	33-51-22	D13124		4		GD03372	DC..	1		YN231-YN501
0470	20	PA		2-4	33-51-22	D10132		4		GD08036	DC..	1		YC051-YD157
0471	20	PA		1-0	33-51-22	SM00070		9		D13124		1		YD158-YD170
0471	20	PA		1-0	33-51-22	D13124		1		SM00070		9		YL951-YL999, YN501-YR328
0471	16	PA		21-1	33-51-22	D13124		1	16	D40100J		4		YN231-YN260
0472	20	PA		1-0	33-51-22	SM00090		9		D13124		2		YD158-YD170
0472	20	PA		1-0	33-51-22	D13124		2		SM00090		9		YL951-YL999
0472	20	PA		1-0	33-51-22	D13124		2		SM00070		9		YN231-YR328
0473	20	PA		6-7	33-51-14	D40044P		3		D40100J		3		YN231-YN501
0474	20	PA		2-4	33-51-14	D40044P		4		GD03814	DC..	1		YC051-YL999, YR301-YR328
0474	20	PA		2-6	33-51-14	D40044P		4		GD03814	DC..	1		YN231-YN501
0475	22	PA		8-11	33-26-11	D40044P		5		SP03522		S		YC051-YL999, YR301-YR328
0475	22	PA		9-1	33-26-11	D40044P		5		SP03522		S		YN231-YN501
0476	20	PA		2-4	33-26-11	D40044P		6		GD03814	AC..	1		YC051-YL999, YR301-YR328
0476	20	PA		2-6	33-26-11	D40044P		6		GD03814	AC..	1		YN231-YN501
0501	16	PA		4-3	33-51-11	D13018		1	16	GD07004	DC..	1		YD158-YL999
0501	16	PA		3-5	33-51-11	D13018		1	16	GD07004	DC..	1		YN231-YN260
0501	16	PA		3-6	33-51-11	D13018		1	16	GD07004	DC..	1		YN501-YR328
0502	20	PA		0-7	33-51-11	D13018		2		SM00021		9		YD158-YD170, YN231-YN501
0502	20	PA		1-5	33-51-11	D13018		2		SM00021		9		YL951-YL999, YR301-YR328
0503	22	PA		34-11	33-51-11	D13018		3		D40096P		14		YD158-YD170
0503	22	PA		35-0	33-51-11	D13018		3		D40096P		14		YL951-YL999, YR301-YR328
0503	22	PA		34-1	33-51-11	D13018		3		D40096P		12		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3140

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3142	286A3142				EMERGENCY EXIT LIGHT - LEFT (continued)										
0504	22		PA		34-11	33-51-11	D13018	4			D40096P	11			YD158-YD170
0504	22		PA		35-0	33-51-11	D13018	4			D40096P	11			YL951-YL999, YR301-YR328
0504	22		PA		34-1	33-51-11	D13018	4			D40096P	11			YN231-YN501
0506	20		PA		0-7	33-51-11	D13018	5			D13018	6			YD158-YR328
0507	20		PA		4-9	33-51-11	D13018	7			GD07004	ST..	1		YD158-YD170
0507	20		PA		3-5	33-51-11	D13018	7			GD07004	ST..	1		YL951-YR328
0509	16		PA		40-8	33-51-12	D13018	9	16		D12032	1			YD158-YL999, YR301-YR328
0510	20		PA		3-9	33-51-21	SM00072		9		D13018	12			YL951-YL999, YR301-YR328
0510	20		PA		2-10	33-51-21	D13018	12			SM00072		9		YN231-YN260
0511	20		PA		18-8	33-51-12	D13018	11			D12048	1			YD158-YL999
0511	20		PA		16-5	33-51-12	D13018	11			D11096	1			YN231-YN260
0511	20		PA		13-7	33-51-12	D13018	11			D14828	A			YR301-YR328
0512	20		PA		2-10	33-51-21	D13018	12			SM00072		9		YD158-YD170, YN501
0513	16		PA		25-3	33-51-12	D13018	13	16		D12046	1			YD158-YD170
0513	16		PA		25-4	33-51-12	D13018	13	16		D12046	1			YL951-YL999
0513	20		PA		20-3	33-51-12	D13018	13			D11100	1			YN231-YN260
0514	20		PA		18-6	33-51-12	D13018	14			D12062	1			YD158-YL999
0514	20		PA		22-9	33-51-12	D13018	14			D14694	A			YR301-YR328
0515	18		PA		15-9	33-51-12	D13018	14	18		D07198J	=1	VS		YN231-YN260
0516	20		PA		30-0	33-51-12	D13018	16			D11326	1			YN231-YN260
0522	20		PA		0-7	33-51-11	D13018	22			SM00021		9		YD158-YD170, YN231-YN501
0522	20		PA		1-5	33-51-11	D13018	22			SM00021		9		YL951-YL999, YR301-YR328
0524	20		PA		0-7	33-51-11	D13018	20			D13018	24			YD158-YR328
0526	20		PA		34-11	33-51-11	D40096P	13			SM00021		9		YD158-YD170
0526	20		PA		34-2	33-51-11	D40096P	13			SM00021		9		YL951-YL999, YR301-YR328
0526	20		PA		34-1	33-51-11	D40096P	13			SM00021		9		YN231-YN501
0551	20		PA		0-7	33-51-21	SM00072		9		D12802	1			YD158-YD170
0551	20		PA		1-0	33-51-21	D12802	1			SM00072		9		YL951-YN260, YR301-YR328
0551	20		PA		0-7	33-51-21	D12802	1			SM00072		9		YN501
0552	20		PA		0-7	33-51-21	SM00072		9		D12802	2			YD158-YD170
0552	20		PA		1-0	33-51-21	D12802	2			SM00072		9		YL951-YN260, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3140

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description		From				To					
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3142	286A3142				EMERGENCY EXIT LIGHT - LEFT (continued)										
0552	20		PA		0-7	33-51-21	D12802				SM00072				YN501
0554	20		PA		3-5	33-51-21	D12802				GD07004	DC..	1		YD158-YD170
0554	20		PA		2-9	33-51-21	D12802				GD07004	DC..	1		YL951-YL999, YR301-YR328
0554	20		PA		2-2	33-51-21	D12802				GD07004	DC..	1		YN231-YN501
0555	20		PA		3-5	33-51-21	D12802				GD07004	DC..	1		YD158-YD170
0555	20		PA		2-9	33-51-21	D12802				GD07004	DC..	1		YL951-YL999, YR301-YR328
0555	20		PA		2-2	33-51-21	D12802				GD07004	DC..	1		YN231-YN501
0570	20		PA		15-9	33-51-12	D07192P	= 1	VG		D13018		9		YN501
0572	20		PA		14-11	33-51-12	D14698		A		D13018		13		YN501
0573	20		PA		9-8	33-51-12	D14698		B		GD03742	DC..	1		YN501
0576	20		PA		24-4	33-51-12	D14702		A		D13018		15		YN501
0576	16		PA		27-5	33-51-13	D14702		A		D10716		16	16	YR301-YR328
0577	16		PA		4-5	33-51-12	D14702		B		GD03732	DC..	1		YN501
0577	16		PA		4-8	33-51-13	D14702		B		GD03728	DC..	1		YR301-YR328
0578	20		PA		23-10	33-51-12	D14698		A		D13018		16		YR301-YR328
0579	16		PA		4-8	33-51-12	D14698		B		GD08012	DC..	1		YR301-YR328
0582	16		PA		28-6	33-51-12	D07194P	= 1	VG		D13018		14	16	YN501
0612	20		PA		17-6	33-51-13	D14710		A		D10716		15		YN501
0612	20		PA		7-3	33-51-13	D14710		A		SM00081			9	YR301-YR328
0613	20		PA		3-11	33-51-13	D14710		B		GD03848	DC..	1		YN501
0613	20		PA		4-7	33-51-13	D14710		B		GD03848	DC..	1		YR301-YR328
0614	20		PA		16-9	33-51-13	D14712		A		D10716		16		YN501
0614	20		PA		6-5	33-51-13	D14712		A		SM00081			9	YR301-YR328
0615	20		PA		2-2	33-51-13	D14712		B		GD03848	DC..	1		YN501
0615	20		PA		2-7	33-51-13	D14712		B		GD03848	DC..	1		YR301-YR328
0618	20		PA		3-8	33-51-13	D14726		A		SM00006			9	YN501
0619	20		PA		3-6	33-51-13	D14726		B		GD03988	DC..	1		YN501
0636	20		PA		2-11	33-51-12	D14692		A		SM00106			9	YN501
0636	20		PA		23-9	33-51-12	D14692		A		D13018		13		YR301-YR328
0637	20		PA		3-6	33-51-12	D14692		B		GD03860	DC..	1		YN501
0637	20		PA		3-3	33-51-12	D14692		B		GD03860	DC..	1		YR301-YR328
0638	20		PA		1-9	33-51-12	D14694		A		SM00106			9	YN501
0639	16		PA		2-5	33-51-12	D14694		B		GD03860	DC..	1		YN501
0641	20		PA		16-5	33-51-14	D14720		A		D10746		16		YN501
0642	20		PA		9-8	33-51-14	D14720		B		GD03764	DC..	1		YN501
2201B	22		PB	GA	6-10	23-31-04	D40044P		2		D40009J			2	YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3140

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3142	286A3142			EMERGENCY EXIT LIGHT - LEFT (continued)											
2201B	22	PB	GA		7-0	23-31-04	D40044P	2			D40009J	2			YN231-YN501
2201R	22	PB	GA		0-0	23-31-04	D40044P	1			D40009J	1			ALL
5501	20	PA			0-7	21-42-11	SM00054		9		SM00030		9		YC051-YL999, YR301-YR328
5512	20	PA			40-2	21-42-11	D40196J	9			SM00030		9		YC051-YL999, YR301-YR328
5512	20	PA			30-2	21-42-11	D40196J	9			SM00030		9		YN231-YN501
5513	20	PA			14-10	21-42-11	SM00030		9		SP00702		9		YN231-YN501
5514	20	PA			6-1	21-42-11	SP00704		9		GD03944	AC..	1		YN231-YN501
5515	20	PA			9-5	21-42-11	SM00060		9		SM00030		9		YC051-YL999, YR301-YR328
5515	20	PA			8-2	21-42-11	SM00030		9		SM00060		9		YN231-YN501
5516	20	PA			3-3	21-42-11	SM00062		9		GD03988	AC..	1		YC051-YL999, YR301-YR328
5516	20	PA			2-2	21-42-11	SM00062		9		GD03988	AC..	1		YN231-YN501
5526	20	PA			16-4	21-42-11	SM00030		9		D12672	= 1	VS		YC051-YL999, YR301-YR328
5526	20	PA			16-2	21-42-11	SM00030		9		D12672	= 1	VS		YN231-YN501
5527	20	PA			3-10	21-42-11	D12674	= 1	VG		GD03754	AC..	1		YC051-YL999, YR301-YR328
5527	20	PA			3-7	21-42-11	D12674	= 1	VG		GD03754	AC..	1		YN231-YN501
5528	20	PA			2-8	21-42-11	SM00060		9		D12664	= 1	VS		YC051-YL999, YR301-YR328
5528	20	PA			5-1	21-42-11	SM00060		9		D12664	= 1	VS		YN231-YN501
5529	20	PA			2-8	21-42-11	SM00062		9		D12666	= 1	VG		YC051-YL999, YR301-YR328
5529	20	PA			5-1	21-42-11	SM00062		9		D12666	= 1	VG		YN231-YN501
5530	20	PA			4-9	21-42-11	SM00060		9		D12552	= 1	VS		YC051-YL999, YR301-YR328
5530	20	PA			7-6	21-42-11	SM00060		9		D12552	= 1	VS		YN231-YN501
5531	20	PA			4-9	21-42-11	SM00062		9		D12554	= 1	VG		YC051-YL999, YR301-YR328
5531	20	PA			7-6	21-42-11	SM00062		9		D12554	= 1	VG		YN231-YN501
5532	20	PA			11-9	21-42-11	SM00030		9		D12668	= 1	VS		YC051-YL999, YR301-YR328
5532	20	PA			11-7	21-42-11	SM00030		9		D12668	= 1	VS		YN231-YN501
5533	20	PA			15-10	21-42-11	D12670	= 1	VG		GD03988	AC..	1		YC051-YL999, YR301-YR328
5533	20	PA			4-5	21-42-11	D12670	= 1	VG		GD03944	AC..	1		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3140

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	
W3142	286A3142			EMERGENCY EXIT LIGHT - LEFT (continued)										
5534	20		PA	11-9	21-42-11	D12708	= 1	VS		SM00054		9		YC051-YL999, YR301-YR328
5535	20		PA	7-10	21-42-11	D12710	= 1	VG		GD03744	AC..	1		YC051-YL999, YR301-YR328
5536	20		PA	0-7	21-42-11	SM00054		9		SM00026		9		YC051-YL999, YR301-YR328
5537	20		PA	4-11	21-42-11	SM00052		9		GD03728	AC..	1		YC051-YL999, YR301-YR328
5538	20		PA	8-4	21-42-11	D12700	= 1	VS		SM00026		9		YC051-YL999, YR301-YR328
5539	20		PA	4-1	21-42-11	D12702	= 1	VG		SM00052		9		YC051-YL999, YR301-YR328
5540	20		PA	10-8	21-42-11	D12576	= 1	VS		SM00026		9		YC051-YL999, YR301-YR328
5541	20		PA	6-10	21-42-11	D12578	= 1	VG		SM00052		9		YC051-YL999, YR301-YR328
5542	20		PA	12-8	21-42-11	D12704	= 1	VS		SM00054		9		YC051-YL999, YR301-YR328
5543	20		PA	3-6	21-42-11	D12706	= 1	VG		GD08000	AC..	1		YC051-YL999, YR301-YR328
5544	20		PA	16-9	21-42-11	SP00270		9		SM00054		9		YC051-YL999, YR301-YR328
5545	20		PA	6-7	21-42-11	SP00260		9		GD08000	AC..	1		YC051-YL999, YR301-YR328
5573	20		PA	18-11	21-42-11	SP00702		9		SM00030		9		YC051-YL999, YR301-YR328
5574	20		PA	6-11	21-42-11	SP00704		9		GD03754	AC..	1		YC051-YL999, YR301-YR328
C-A				0-0	21-42-11	SP00702		9		M02177	= W/B			ALL
C-B				0-0	21-42-11	SP00704		9		M02177	= WHT		ALL	
E-A				0-0	21-42-11	SP00270		9		M02183	= W/B			YC051-YL999, YR301-YR328
E-B				0-0	21-42-11	SP00260		9		M02183	= WHT		YC051-~ YL999, YR301-~ YR328	
F-A				0-0	52-71-13	SP00802		9		M02219	= BLK			ALL
F-B				0-0	52-71-13	SP00804		9		M02219	= BLK			ALL

WIRE LIST

D280A108

91-21-11

Section W3140

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description FT-IN Diagram	From				To				
	GA	CO	TY		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3142	286A3142			EMERGENCY EXIT LIGHT - LEFT (continued)									
G-A				0-0	52-71-13	SP00814		9	S01105	= RED			ALL
G-B				0-0	52-71-13	SP00816		9	S01105	= WHT		ALL	
H-A				0-0	52-71-13	SP00806		9	S01112	= WHT		ALL	
H-B				0-0	52-71-13	SP00808		9	S01112	= WHT		ALL	
I-A				0-0	52-71-13	SP00810		9	S01104	= RED			ALL
I-B				0-0	52-71-13	SP00812		9	S01104	= WHT		ALL	
N-A				0-0	52-71-13	SP00818		9	M02220	= BLK			YC051-YL999, YR301-YR328
N-B				0-0	52-71-13	SP00820		9	M02220	= BLK			YC051-YL999, YR301-YR328
P-A				0-0	52-71-13	SP00826		9	S01108	= RED			YC051-YL999, YR301-YR328
P-B				0-0	52-71-13	SP00828		9	S01108	= WHT		YC051-~ YL999, YR301-~ YR328	
Q-A				0-0	52-71-13	SP00830		9	S01109	= RED			YC051-YL999, YR301-YR328
Q-B				0-0	52-71-13	SP00832		9	S01109	= WHT		YC051-~ YL999, YR301-~ YR328	
R-A				0-0	52-71-13	SP00822		9	S01113	= WHT		YC051-~ YL999, YR301-~ YR328	
R-B				0-0	52-71-13	SP00824		9	S01113	= WHT		YC051-~ YL999, YR301-~ YR328	
W3143	286A3143			GLIDE SLOPE ANT RIGHT - STA 178 TO E1-3 SHELF									
001CO			AA	0-0	34-31-21	D03319		= C1	D04027J	= C1			ALL
001CX		0F	AA	14-7	34-31-21	D03319		= A1	D04027J	= A1			ALL

WIRE LIST

D280A108

91-21-11
Section W3140
Page 18
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type
W3144	286A3144				P18 TO FWD AND AFT LAVATORY										
0001	20		PA		1-6	33-25-21	D11722		1		SM00021		S		YC051-YL999, YR301-YR328
0001	20		PA		1-1	33-25-21	D11722		1		SM00021		S		YN231-YN501
0002	18		PA		7-3	33-25-21	D11722		2		GD03734	AC..	1D		YC051-YL999, YR301-YR328
0002	18		PA		2-10	33-25-21	D11722		2		GD03734	AC..	1D		YN231-YN501
0003	18		PA		1-6	33-25-21	D11722		3		SM00022		S		YC051-YL999, YR301-YR328
0003	18		PA		1-1	33-25-21	D11722		3		SM00022		S		YN231-YN501
0007	20		PA		4-5	33-26-31	D40220P		7		SM00007		S		ALL
0008	22		PA		4-5	33-26-31	D40220P		8		SM00008		S		YC051-YN260
0008	20		PA		4-5	33-26-31	D40220P		8		SM00008		S		YN501-YR328
0013	20		PA		94-8	SPARE	D40220P		13		D03738	CAP	Y		YC051-YL999, YR301-YR328
0013	20		PA		76-5	SPARE	D40220P		13		D03738	CAP	Y		YN231-YN501
0014	20		PA		94-8	SPARE	D40220P		14		D03738	CAP	Y		YC051-YL999, YR301-YR328
0014	20		PA		76-5	SPARE	D40220P		14		D03738	CAP	Y		YN231-YN501
0015	20		PA		4-6	SPARE	D40220P		15		D03732	CAP	Y		YC051-YC052, YL951-YL999, YR301-YR328
0015	20		PA		4-4	SPARE	D40220P		15		D03732	CAP	Y		YC053-YD170
0015	20		PA		5-11	SPARE	D40220P		15		D03732	CAP	Y		YN231-YN501
0016	20		PA		4-6	SPARE	D40220P		16		D03732	CAP	Y		YC051-YC052, YL951-YL999, YR301-YR328
0016	20		PA		4-4	SPARE	D40220P		16		D03732	CAP	Y		YC053-YD170
0016	20		PA		5-11	SPARE	D40220P		16		D03732	CAP	Y		YN231-YN501
0020	20		PA		87-5	38-32-13	D40220P		20		SP03060		S		YC051-YL999, YR301-YR328
0020	20		PA		67-11	38-32-13	D40220P		20		SP03060		S		YN231-YN260
0020	20		PA		68-2	38-32-13	D40220P		20		SP03060		S		YN501
0021	16		PA		9-9	SPARE	D40220P		21		D40216P	7			YC051-YC052, YL951-YL999, YR301-YR328
0021	16		PA		9-9	25-29-11	D40220P		21		D40216P	7			YC053-YD170
0025	20		PA		94-8	SPARE	D40220P		25		D03738	CAP	Y		YC051-YD170
0026	20		PA		4-6	SPARE	D40220P		26		D03732	CAP	Y		YC051-YD170
0027	24		PK		2-11	26-14-11	D40220P		27		D40090P	6			YC051-YD170

WIRE LIST

D280A108

91-21-11

Section W3140

Page 19

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3144	286A3144				P18 TO FWD AND AFT LAVATORY (continued)										
0027	22	PA			4-5	26-14-11	D40220P	27			SM00023		S		YL951-YR328
0029	20	PA			87-2	33-26-31	SM00007		S		SM00029		S		YC051-YL999
0029	20	PA			71-2	33-26-31	SM00007		S		SM00029		S		YN231-YN260
0032	20	PA			8-1	38-32-12	D40150P	12			SM00003		S		YC051-YL999, YN501-YR328
0032	20	PA			9-7	38-32-12	D40150P	12			SM00003		S		YN231-YN260
0033	18	PA			8-1	38-32-12	D40150P	2			SM00001		S		YC051-YL999, YN501-YR328
0033	18	PA			9-7	38-32-12	D40150P	2			SM00001		S		YN231-YN260
0035	22	PA			87-2	26-14-11	SM00023		S		SM00035		S		YL951-YL999, YR301-YR328
0053	20	PA			7-6	33-26-31	D40184P	3			SM00007		S		YC051-YL999
0053	20	PA			7-5	33-26-31	D40184P	3			SM00007		S		YN231-YN260
0056	22	PA			87-2	33-26-31	SM00008		S		SM00056		S		YC051-YL999
0056	20	PA			87-2	33-26-31	SM00008		S		SM00056		S		YR301-YR328
0057	24	PK			87-2	26-14-11	SM00118		S		SM00318		S		YC051-YD170
0058	24	PK			87-2	26-14-11	SM00119		S		SM00319		S		YC051-YD170
0059	24	PK			87-2	26-14-11	SM00121		S		SM00321		S		YC051-YD170
0060	24	PK			87-2	26-14-11	SM00141		S		SM00341		S		YC051-YD170
0061	24	PK			87-2	26-14-11	SM00142		S		SM00342		S		YC051-YD170
0063	20	PA			4-5	33-26-31	D40186P	3			SM00029		S		YC051-YL999
0063	20	PA			8-4	33-26-31	D40186P	3			SM00029		S		YN231-YN260
0065	24	PK			3-3	26-14-11	D40090P	1			SM00118		S		YC051-YD170
0066	24	PK			3-3	26-14-11	D40090P	2			SM00119		S		YC051-YD170
0067	24	PK			3-3	26-14-11	D40090P	4			SM00121		S		YC051-YD170
0068	24	PK			3-3	26-14-11	D40090P	5			SM00141		S		YC051-YD170
0069	24	PK			3-3	26-14-11	D40090P	10			SM00142		S		YC051-YD170
0071	20	PA			10-3	33-25-21	D40216P	1			SM00021		S		YC051-YL999, YR301-YR328
0071	20	PA			10-7	33-25-21	D40216P	1			SM00021		S		YN231-YN501
0072	18	PA			10-3	33-25-21	D40216P	2			SM00022		S		YC051-YL999, YR301-YR328
0072	18	PA			10-7	33-25-21	D40216P	2			SM00022		S		YN231-YN501
0076	18	CQ			1-5	35-21-21	D07176P	=1	VR		SM00031		S		ALL
0079	18	CQ			2-8	35-21-21	D07170J	=1	VY		SM00031		S		YC051-YL999, YN501-YR328
0079	18	CQ			2-7	35-21-21	D07170J	=1	VY		SM00031		S		YN231-YN260
0083	22	PA			3-7	33-27-22	D40270J	11			SP03490		S		YC051-YL999, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W3140

Page 20

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description		From				To					
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3144	286A3144			P18 TO FWD AND AFT LAVATORY (continued)											
0083	22		PA		3-4	33-27-22	D40270J	11			SP03490		S		YN231-YN260
0085	22		PA		3-11	33-27-22	D40270J	5			SM00085		S		YC051-YL999, YR301-YR328
0086	18		CQ		3-11	35-21-21	D40270J	6			SM00032		S		YC051-YL999, YN501-YR328
0086	18		CQ		3-3	35-21-21	D40270J	6			SM00032		S		YN231-YN260
0089	18		CQ		3-11	35-21-21	D07172J	= 1	VY		SM00032		S		YC051-YL999, YN501-YR328
0089	18		CQ		3-6	35-21-21	D07172J	= 1	VY		SM00032		S		YN231-YN260
0090	18		PA		6-10	33-25-11	D40116J	2			SM00090		S		YC051-YD170, YR301-YR328
0090	18		PA		6-1	33-25-11	D40116J	2			SM00090		S		YL951-YL999
0091	18		PA		0-7	38-32-12	SM00001		S		SM00091		S		YC051-YL999, YR301-YR328
0093	20		PA		0-7	38-32-12	SM00003		S		SM00093		S		YC051-YL999, YR301-YR328
0095	20		PA		14-9	33-25-22	D03802	5			D40116J	10			YC051-YL999, YR301-YR328
0095	20		PA		14-8	33-25-22	D03802	5			D40116J	10			YN231-YN501
0096	18		PA		14-9	33-25-22	D03802	6			D40116J	9			YC051-YL999, YR301-YR328
0096	18		PA		14-8	33-25-22	D03802	6			D40116J	9			YN231-YN501
0097	18		PA		2-8	33-25-22	D03802	7			GD03736	AC..	1		YC051-YL999, YR301-YR328
0097	18		PA		2-5	33-25-22	D03802	7			GD03736	AC..	1		YN231-YN501
0101	18		PA		2-2	33-26-31	D03732	1			GD11100	ST..	1		ALL
0102	22		PA		4-4	33-27-11	D03732	2			D40220P	28			ALL
0103	20		PA		2-6	33-26-31	D03732	3			SM00007		S		ALL
0104	20		PA		9-6	33-26-31	D03732	4			D40184P	1			YC051-YL999
0104	20		PA		9-5	33-26-31	D03732	4			D40184P	1			YN231-YN260
0104	20		PA		9-6	33-26-31	D03732	4			D07162P	= 1	VG		YN501-YR328
0106	22		PA		2-6	33-26-31	D03732	6			SM00008		S		YC051-YN260
0106	20		PA		2-6	33-26-31	D03732	6			SM00008		S		YN501-YR328
0115	18		CQ		2-2	35-21-21	D03732	15			GD11100	DC..	1		ALL
0117	22		PA		6-11	33-27-11	D03732	17			SP03498		S		YC051-YL999, YN501-YR328
0117	22		PA		7-0	33-27-11	D03732	17			SP03498		S		YN231-YN260
0118	24		PK		2-6	26-14-11	D03732	18			SM00118		S		YC051-YD170
0119	24		PK		2-6	26-14-11	D03732	19			SM00119		S		YC051-YD170

WIRE LIST

D280A108

91-21-11

Section W3140

Page 21

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity			
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice	
W3144	286A3144				P18 TO FWD AND AFT LAVATORY (continued)											
0120	24		PK		3-2	26-14-11	D40090P		7		D03732	20			YC051-YD170	
0121	24		PK		2-6	26-14-11	D03732		21		SM00121		S		YC051-YD170	
0122	18		CQ		2-6	35-21-21	D03732		22		SM00031		S		ALL	
0123	22		PA		2-6	26-14-11	D03732		23		SM00023		S		YL951-YR328	
0127	18		PA		7-10	33-25-11	D03732		27		D40216P	3			YC051-YL999, YR301-YR328	
0127	18		PA		7-8	33-25-11	D03732		27		D40216P	3			YN231-YN501	
0128	18		PA		2-2	33-25-11	D03732		28		GD11100	AC..	1		ALL	
0129	22		PA		4-4	33-27-11	D03732		29		D40220P	29			ALL	
0130	18		PA		2-2	33-26-31	D03732		30		GD11100	ST..	1		ALL	
0131	18		PA		89-2	38-32-12	D03732		31		SM00001		S		YC051-YL999, YR301-YR328	
0131	18		PA		71-0	38-32-12	D03732		31		SM00001		S		YN231-YN260	
0131	18		PA		69-11	38-32-12	D03732		31		SM00001		S		YN501	
0132	20		PA		11-11	33-25-21	D03732		32		SM00021		S		YC051-YL999, YR301-YR328	
0132	20		PA		12-4	33-25-21	D03732		32		SM00021		S		YN231-YN501	
0133	18		PA		11-11	33-25-21	D03732		33		SM00022		S		YC051-YL999, YR301-YR328	
0133	18		PA		12-4	33-25-21	D03732		33		SM00022		S		YN231-YN501	
0138	22		PA		4-4	38-21-11	D03732		38		D40220P	3			ALL	
0139	18		PA		2-2	33-26-31	D03732		39		GD11100	AC..	1		ALL	
0140	18		PA		2-2	33-26-31	D03732		40		GD11100	AC..	1		ALL	
0141	24		PK		2-6	26-14-11	D03732		41		SM00141		S		YC051-YD170	
0142	24		PK		2-6	26-14-11	D03732		42		SM00142		S		YC051-YD170	
0143	20		PA		89-2	38-32-12	D03732		43		SM00003		S		YC051-YL999, YR301-YR328	
0143	20		PA		71-0	38-32-12	D03732		43		SM00003		S		YN231-YN260	
0143	20		PA		69-11	38-32-12	D03732		43		SM00003		S		YN501	
0301	18		PA		4-2	33-26-31	D03738		1		GD03864	ST..	1		ALL	
0302	22		PA		3-5	33-27-22	D03738		2		D40270J	10			YC051-YL999, YN501-YR328	
0302	22		PA		3-3	33-27-22	D03738		2		D40270J	10			YN231-YN260	
0303	20		PA		4-0	33-26-31	D03738		3		SM00029		S		YC051-YL999	
0303	20		PA		0-7	33-26-31	D03738		3		SM00029		S		YN231-YN260	
0303	20		PA		71-5	33-26-31	D03738		3		SM00007		S		YN501	
0303	20		PA		90-7	33-26-31	D03738		3		SM00007		S		YR301-YR314	
0303	20		PA		87-2	33-26-31	SM00066		S		SM00007		S		YR315-YR328	
0304	22		PA		13-1	33-26-31	D03738		4		D03740	3			YC051-YL999	

WIRE LIST

D280A108

91-21-11

Section W3140

Page 22

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3144		286A3144			P18 TO FWD AND AFT LAVATORY (continued)											
0304		20		PA		8-4	33-26-31	D03738				D40186P	1			YN231-YN260
0304		20		PA		8-4	33-26-31	D03738				D07164P	=1	VG		YN501
0304		20		PA		13-1	33-26-31	D03738				D03740	3			YR301-YR314
0306		22		PA		4-0	33-26-31	D03738				SM00056		S		YC051-YL999
0306		22		PA		71-2	33-26-31	D03738				SM00008		S		YN231-YN260
0306		20		PA		71-5	33-26-31	D03738				SM00008		S		YN501
0306		20		PA		4-0	33-26-31	D03738				SM00056		S		YR301-YR328
0310		20		PA		3-7	33-51-22	D03738				SP00412		S		ALL
0311		20		PA		4-2	33-51-22	D03738				GD03864	DC..	1		ALL
0315		18		CQ		4-2	35-21-21	D03738				GD03864	DC..	1		ALL
0317		22		PA		3-7	33-27-22	D03738				SP03492		S		ALL
0318		24		PK		4-0	26-14-11	D03738				SM00318		S		YC051-YD170
0319		24		PK		4-0	26-14-11	D03738				SM00319		S		YC051-YD170
0320		24		PK		93-4	26-14-11	D40090P				D03738	20			YC051-YD170
0321		24		PK		4-0	26-14-11	D03738				SM00321		S		YC051-YD170
0322		18		CQ		4-0	35-21-21	D03738				SM00032		S		YC051-YL999, YN501-YR328
0322		18		CQ		0-7	35-21-21	D03738				SM00032		S		YN231-YN260
0323		22		PA		4-0	26-14-11	D03738				SM00035		S		YL951-YL999, YR301-YR328
0323		22		PA		71-2	26-14-11	D03738				SM00023		S		YN231-YN260
0323		22		PA		71-5	26-14-11	D03738				SM00023		S		YN501
0327		18		PA		0-7	33-25-11	D03738				SM00090		S		YC051-YD170, YR301-YR328
0327		18		PA		1-3	33-25-11	D03738				SM00090		S		YL951-YL999
0327		18		PA		6-8	33-25-11	D03738				D40116J	2			YN231-YN501
0328		18		PA		4-2	33-25-11	D03738				GD03864	AC..	1		ALL
0329		22		PA		4-0	33-27-22	D03738				SM00085		S		YC051-YL999, YR301-YR328
0329		22		PA		3-3	33-27-22	D03738				D40270J	5			YN231-YN260
0329		22		PA		3-5	33-27-22	D03738				D40270J	5			YN501
0330		18		PA		4-2	33-26-31	D03738				GD03864	ST..	1		ALL
0331		18		PA		4-0	38-32-12	D03738				SM00091		S		YC051-YL999, YR301-YR328
0331		18		PA		2-8	38-32-12	D03738				SM00001		S		YN231-YN260
0331		18		PA		4-0	38-32-12	D03738				SM00001		S		YN501
0338		22		PA		94-6	38-21-11	D03738				D40220P	4			YC051-YL999, YR301-YR328
0338		22		PA		75-0	38-21-11	D03738				D40220P	4			YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W3140

Page 23

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3144	286A3144				P18 TO FWD AND AFT LAVATORY (continued)										
0338	22		PA		75-3	38-21-11	D03738		38		D40220P		4		YN501
0339	18		PA		4-2	33-26-31	D03738		39		GD03864	AC..	1		ALL
0340	18		PA		4-2	33-26-31	D03738		40		GD03864	AC..	1		ALL
0341	24		PK		4-0	26-14-11	D03738		41		SM00341		S		YC051-YD170
0342	24		PK		4-0	26-14-11	D03738		42		SM00342		S		YC051-YD170
0343	20		PA		4-0	38-32-12	D03738		43		SM00093		S		YC051-YL999, YR301-YR328
0343	20		PA		2-8	38-32-12	D03738		43		SM00003		S		YN231-YN260
0343	20		PA		4-0	38-32-12	D03738		43		SM00003		S		YN501
0351	18		PA		3-7	33-26-31	D03740		1		GD04100	ST..	1		YC051-YL999, YR301-YR328
0352	22		PA		7-11	33-27-32	D03740		2		D40272J		10		YC051-YL999, YR301-YR328
0354	20		PA		17-6	33-26-31	D40186P		1		D03740		4		YC051-YL999
0354	20		PA		17-6	33-26-31	D07164P		= 1	VG	D03740		4		YR301-YR314
0354	20		PA		17-3	33-26-31	D07108J		= 1	VS	D03740		4		YR315-YR328
0356	22		PA		13-8	33-26-31	SM00056			S	D03740		6		YC051-YL999
0356	20		PA		13-8	33-26-31	SM00056			S	D03740		6		YR301-YR328
0365	18		CQ		3-7	35-21-31	D03740		15		GD04100	DC..	1		YC051-YL999, YR301-YR328
0367	22		PA		13-3	33-27-32	D03740		17		SP03492		S		YC051-YL999, YR301-YR328
0368	24		PK		13-8	26-14-11	D03740		18		SM00318		S		YC051-YD170
0369	24		PK		13-8	26-14-11	D03740		19		SM00319		S		YC051-YD170
0370	24		PK		102-6	26-14-11	D40090P		9		D03740		20		YC051-YD170
0371	24		PK		13-8	26-14-11	D03740		21		SM00321		S		YC051-YD170
0372	18		CQ		7-11	35-21-31	D03740		22		D40272J		16		YC051-YL999, YR301-YR328
0373	22		PA		13-8	26-14-11	D03740		23		SM00035		S		YL951-YL999, YR301-YR328
0377	18		PA		13-1	33-25-11	D03740		27		SM00090		S		YC051-YD170, YR301-YR328
0377	18		PA		12-5	33-25-11	D03740		27		SM00090		S		YL951-YL999
0378	18		PA		3-7	33-25-11	D03740		28		GD04100	AC..	1		YC051-YL999, YR301-YR328
0379	22		PA		13-8	33-27-32	D03740		29		SM00085		S		YC051-YL999, YR301-YR328
0380	18		PA		3-7	33-26-31	D03740		30		GD04100	ST..	1		YC051-YL999, YR301-YR328

WIRE LIST
D280A108

91-21-11
Section W3140
Page 24
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W3144	286A3144			P18 TO FWD AND AFT LAVATORY (continued)										
0381	18		PA		13-8 38-32-12	D03740	31			SM00091		S		YC051-YL999, YR301-YR328
0388	22		PA		103-7 38-21-11	D03740	38			D40220P	2			YC051-YL999, YR301-YR328
0389	18		PA		3-7 33-26-31	D03740	39			GD04100	AC..	1		YC051-YL999, YR301-YR328
0390	18		PA		3-7 33-26-31	D03740	40			GD04100	AC..	1		YC051-YL999, YR301-YR328
0391	24		PK		13-8 26-14-11	D03740	41			SM00341		S		YC051-YD170
0392	24		PK		13-8 26-14-11	D03740	42			SM00342		S		YC051-YD170
0393	20		PA		13-8 38-32-12	D03740	43			SM00093		S		YC051-YL999, YR301-YR328
0518	20		PA		4-0 33-26-31	SM00066		S		D03738	3			YR315-YR328
0519	20		PA		9-8 33-26-31	D03738	4			D07106J	=1	VY		YR315-YR328
0520	20		PA		13-8 33-26-31	SM00066		S		D03740	3			YR315-YR328
1161	20		PA		3-2 23-70-11	D40349J	3			GD03734	ST..	1A		YL951-YL999, YR301-YR328
1161	20		PA		6-9 23-70-11	D40349J	3			GD03734	ST..	1A		YN231-YN260
2261B	20		PB	MK	11-2 23-70-11	D40349J	2			D40220P	26			YL951-YR328
2261R	20		PB	MK	0-0 23-70-11	D40349J	1			D40220P	25			YL951-YR328
2401B	22		PB	OA	6-11 23-31-02	D03732	14			SP00135		S		YC051-YL999, YN501-YR328
2401B	22		PB	OA	7-0 23-31-02	D03732	14			SP00135		S		YN231-YN260
2401R	22		PB	OA	0-0 23-31-02	D03732	13			SP00133		S		ALL
2403B	22		PB	OC	3-5 23-31-02	D03738	14			D40270J	16			YC051-YL999, YN501-YR328
2403B	22		PB	OC	3-3 23-31-02	D03738	14			D40270J	16			YN231-YN260
2403R	22		PB	OC	0-0 23-31-02	D03738	13			D40270J	15			ALL
2404B	22		PB	OD	7-11 23-31-03	D03740	14			D40272J	12			YC051-YL999, YR301-YR328
2404R	22		PB	OD	0-0 23-31-03	D03740	13			D40272J	15			YC051-YL999, YR301-YR328
5501	22		CQ		0-7 21-42-11	D10770	3			SM00041		S		YC051-YL999, YR301-YR328
5501	22		PA		1-0 21-42-11	D10770	3			SM00041		S		YN231-YN501
5502	22		CQ		11-11 21-42-11	D10770	1			D40116J	8			YC051-YL999, YR301-YR328
5502	22		PA		11-8 21-42-11	D10770	1			D40116J	8			YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3140

Page 25

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3144	286A3144				P18 TO FWD AND AFT LAVATORY (continued)										
5503	20		PA		4-5	21-42-11	D10770		4		GD03772	ST..	1		YC051-YL999, YR301-YR328
5503	20		PA		4-7	21-42-11	D10770		4		GD03772	ST..	1		YN231-YN501
5504	22		CQ		0-7	21-42-11	D10770		2		SM00041		S		YC051-YL999, YR301-YR328
5504	22		PA		1-0	21-42-11	D10770		2		SM00041		S		YN231-YN501
5507	22		CQ		11-11	21-42-11	D40116J		7		SM00041		S		YC051-YL999, YR301-YR328
5507	22		PA		11-2	21-42-11	D40116J		7		SM00041		S		YN231-YN501
W3146	286A3146				FLUORESCENT LIGHTING - CEILING LEFT & RIGHT										
0011	18		PA		7-8	33-22-21	D11900		1		SM00001		S		YC051-YL999
0011	18		PA		7-6	33-22-21	D11900		1		SM00001		S		YN231-YN260
0012	18		PA		5-3	33-22-21	D11900		2		GD03860	AC..	1		YC051-YL999
0012	18		PA		6-0	33-22-21	D11900		2		GD03860	AC..	1		YN231-YN260
0013	18		PA		5-3	33-22-21	D11900		3		GD03860	ST..	1		YC051-YL999
0013	18		PA		6-0	33-22-21	D11900		3		GD03860	ST..	1		YN231-YN260
0014	24		PK		7-8	33-22-21	D11900		4		SM00004		S		YD158-YD170, YN231-YN260
0014	24		PK		15-3	33-22-21	D11900		4		SM00004		S		YL951-YL999
0015	24		PK		7-8	33-22-21	D11900		5		SM00005		S		YC051-YN260
0016	24		PK		7-8	33-22-21	D11900		6		SM00006		S		YC051-YN260
0021	18		PA		10-11	33-22-21	D11970		1		SM00021		S		YC051-YL999
0021	18		PA		8-0	33-22-21	D11902		1		SM00021		S		YN231-YN260
0022	18		PA		4-7	33-22-21	D11970		2		GD03866	AC..	1		YC051-YL999
0022	18		PA		6-11	33-22-21	D11902		2		GD03870	AC..	1		YN231-YN260
0023	18		PA		4-7	33-22-21	D11970		3		GD03866	ST..	1		YC051-YL999
0023	18		PA		6-11	33-22-21	D11902		3		GD03870	ST..	1		YN231-YN260
0024	24		PK		10-11	33-22-21	D11970		4		SM00024		S		YC051-YD157
0025	24		PK		10-11	33-22-21	D11970		5		SM00025		S		YC051-YL999
0025	24		PK		8-4	33-22-21	D11902		5		SM00025		S		YN231-YN260
0026	24		PK		10-11	33-22-21	D11970		6		SM00026		S		YC051-YL999
0026	24		PK		8-4	33-22-21	D11902		6		SM00026		S		YN231-YN260
0027	18		PA		41-1	SPARE	D40110J		2		D40984J	CAP	Y		YD158-YD170
0031	18		PA		4-1	33-22-21	D11972		1		SM00021		S		YC051-YL999
0031	18		PA		6-5	33-22-21	D11904		1		SM00021		S		YN231-YN260
0032	18		PA		6-1	33-22-21	D11972		2		GD08010	AC..	1		YC051-YL999
0032	18		PA		9-6	33-22-21	D11904		2		GD03844	AC..	1		YN231-YN260
0033	18		PA		6-1	33-22-21	D11972		3		GD08010	ST..	1		YC051-YL999

WIRE LIST

D280A108

91-21-11

Section W3140

Page 26

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3146		286A3146					FLUORESCENT LIGHTING - CEILING LEFT & RIGHT (continued)								
	0033	18	PA		9-6	33-22-21	D11904		3		GD03844	ST..	1		YN231-YN260
	0035	24	PK		4-1	33-22-21	D11972		5		SM00025		S		YC051-YL999
	0035	24	PK		7-1	33-22-21	D11904		5		SM00025		S		YN231-YN260
	0036	24	PK		4-1	33-22-21	D11972		6		SM00026		S		YC051-YL999
	0036	24	PK		7-1	33-22-21	D11904		6		SM00026		S		YN231-YN260
	0041	18	PA		10-3	33-22-21	D11978		1		SM00041		S		YC051-YL999
	0041	18	PA		6-6	33-22-21	D11906		1		SM00041		S		YN231-YN260
	0042	18	PA		4-1	33-22-21	D11978		2		GD03744	AC..	1		YC051-YL999
	0042	18	PA		3-2	33-22-21	D11906		2		GD03728	AC..	1		YN231-YN260
	0043	18	PA		4-1	33-22-21	D11978		3		GD03744	ST..	1		YC051-YL999
	0043	18	PA		3-2	33-22-21	D11906		3		GD03728	ST..	1		YN231-YN260
	0044	24	PK		10-3	33-22-21	D11978		4		SM00044		S		YC051-YD157
	0044	24	PK		6-7	33-22-21	D11906		4		SM00044		S		YN231-YN260
	0045	24	PK		10-3	33-22-21	D11978		5		SM00045		S		YC051-YL999
	0045	24	PK		6-7	33-22-21	D11906		5		SM00045		S		YN231-YN260
	0046	24	PK		10-3	33-22-21	D11978		6		SM00046		S		YC051-YL999
	0046	24	PK		6-7	33-22-21	D11906		6		SM00046		S		YN231-YN260
	0051	18	PA		3-1	33-22-21	D11980		1		SM00041		S		YC051-YL999
	0051	18	PA		8-6	33-22-21	D11908		1		SM00041		S		YN231-YN260
	0052	18	PA		2-5	33-22-21	D11980		2		GD04004	AC..	1		YC051-YL999
	0052	18	PA		7-4	33-22-21	D11908		2		GD04004	AC..	1		YN231-YN260
	0053	18	PA		2-5	33-22-21	D11980		3		GD04004	ST..	1		YC051-YL999
	0053	18	PA		7-4	33-22-21	D11908		3		GD04004	ST..	1		YN231-YN260
	0054	24	PK		3-1	33-22-21	D11980		4		SM00044		S		YD158-YL999
	0055	24	PK		3-1	33-22-21	D11980		5		SM00045		S		YC051-YL999
	0055	24	PK		8-4	33-22-21	D11908		5		SM00045		S		YN231-YN260
	0056	24	PK		3-1	33-22-21	D11980		6		SM00046		S		YC051-YL999
	0056	24	PK		8-4	33-22-21	D11908		6		SM00046		S		YN231-YN260
	0061	18	PA		4-6	33-22-22	D11982		1		SM00061		S		YC051-YL999
	0061	18	PA		8-2	33-22-22	D11910		1		SM00061		S		YN231-YN260
	0062	18	PA		7-8	33-22-22	D11982		2		GD03848	AC..	1		YC051-YL999
	0062	18	PA		5-5	33-22-22	D11910		2		GD03848	AC..	1		YN231-YN260
	0063	18	PA		7-8	33-22-22	D11982		3		GD03848	ST..	1		YC051-YL999
	0063	18	PA		5-5	33-22-22	D11910		3		GD03848	ST..	1		YN231-YN260
	0064	24	PK		4-6	33-22-22	D11982		4		SM00064		S		YC051-YD157
	0065	24	PK		4-6	33-22-22	D11982		5		SM00065		S		YC051-YL999
	0065	24	PK		8-3	33-22-22	D11910		5		SM00065		S		YN231-YN260
	0066	24	PK		4-6	33-22-22	D11982		6		SM00066		S		YC051-YL999
	0066	24	PK		8-3	33-22-22	D11910		6		SM00066		S		YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W3140

Page 27

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W3146	286A3146				FLUORESCENT LIGHTING - CEILING LEFT & RIGHT (continued)												
0071	18		PA		7-4	33-22-22	D11984			1			SM00061		S		YC051-YL999
0071	18		PA		7-11	33-22-22	D11912			1			SM00061		S		YN231-YN260
0072	18		PA		3-5	33-22-22	D11984			2			GD08020	AC..	1		YC051-YL999
0072	18		PA		5-4	33-22-22	D11912			2			GD03850	AC..	1		YN231-YN260
0073	18		PA		3-5	33-22-22	D11984			3			GD08020	ST..	1		YC051-YL999
0073	18		PA		5-4	33-22-22	D11912			3			GD03850	ST..	1		YN231-YN260
0074	24		PK		22-4	33-22-22	D11912			4			SM00044		S		YN231-YN260
0075	24		PK		7-4	33-22-22	D11984			5			SM00065		S		YC051-YL999
0075	24		PK		8-6	33-22-22	D11912			5			SM00065		S		YN231-YN260
0076	24		PK		7-4	33-22-22	D11984			6			SM00066		S		YC051-YL999
0076	24		PK		8-6	33-22-22	D11912			6			SM00066		S		YN231-YN260
0081	18		PA		4-4	33-22-22	D11914			1			SM00081		S		YC051-YL999
0081	18		PA		4-8	33-22-22	D11914			1			SM00081		S		YN231-YN260
0082	18		PA		6-4	33-22-22	D11914			2			GD03990	AC..	1		YC051-YL999
0082	18		PA		7-6	33-22-22	D11914			2			GD03990	AC..	1		YN231-YN260
0083	18		PA		6-4	33-22-22	D11914			3			GD03990	ST..	1		YC051-YL999
0083	18		PA		7-6	33-22-22	D11914			3			GD03990	ST..	1		YN231-YN260
0085	24		PK		4-4	33-22-22	D11914			5			SM00085		S		YC051-YD157, YL951-YL999
0085	24		PK		7-4	33-22-22	D11914			5			SM00075		S		YD158-YD170
0085	24		PK		5-0	33-22-22	D11914			5			SM00085		S		YN231-YN260
0086	24		PK		4-4	33-22-22	D11914			6			SM00086		S		YC051-YD157, YL951-YL999
0086	24		PK		7-4	33-22-22	D11914			6			SM00076		S		YD158-YD170
0086	24		PK		5-0	33-22-22	D11914			6			SM00086		S		YN231-YN260
0091	18		PA		6-4	33-22-22	D11916			1			SM00081		S		YC051-YL999
0091	18		PA		7-2	33-22-22	D11916			1			SM00081		S		YN231-YN260
0092	18		PA		4-5	33-22-22	D11916			2			GD04006	AC..	1		YC051-YL999
0092	18		PA		5-1	33-22-22	D11916			2			GD04006	AC..	1		YN231-YN260
0093	18		PA		4-5	33-22-22	D11916			3			GD04006	ST..	1		YC051-YL999
0093	18		PA		5-1	33-22-22	D11916			3			GD04006	ST..	1		YN231-YN260
0094	24		PK		25-1	33-22-22	D11916			4			SM00064		S		YC051-YD157
0095	24		PK		6-4	33-22-22	D11916			5			SM00085		S		YC051-YL999
0095	24		PK		6-6	33-22-22	D11916			5			SM00085		S		YN231-YN260
0096	24		PK		6-4	33-22-22	D11916			6			SM00086		S		YC051-YL999
0096	24		PK		6-6	33-22-22	D11916			6			SM00086		S		YN231-YN260
0101	18		PA		10-11	33-22-22	D40038P			1			SM00081		S		YC051-YL999
0101	18		PA		11-5	33-22-22	D40038P			1			SM00081		S		YN231-YN260
0102	18		PA		5-3	33-22-22	D40038P			2			GD03770	AC..	1		YC051-YL999

WIRE LIST

D280A108

91-21-11

Section W3140

Page 28

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3146		286A3146					FLUORESCENT LIGHTING - CEILING LEFT & RIGHT (continued)								
	0102	18	PA		6-0	33-22-22	D40038P		2		GD03770	AC..	1		YN231-YN260
	0103	18	PA		5-3	33-22-22	D40038P		3		GD03770	ST..	1		YC051-YL999
	0103	18	PA		6-0	33-22-22	D40038P		3		GD03770	ST..	1		YN231-YN260
	0105	24	PK		10-11	33-22-22	D40038P		5		SM00085		S		YC051-YN260
	0106	24	PK		10-11	33-22-22	D40038P		6		SM00086		S		YC051-YN260
	0107	20	PA		4-11	33-26-31	D40038P		7		D40186J		3		YC051-YN260
	0108	18	PA		5-3	33-26-31	D40038P		8		GD03770	AC..	1		YC051-YL999
	0108	18	PA		6-0	33-26-31	D40038P		8		GD03770	AC..	1		YN231-YN260
	0109	20	PA		4-11	33-26-31	D40038P		9		D40186J		1		YC051-YN260
	0131	18	PA		8-7	33-22-21	D11974		1		SM00031		S		YC051-YL999
	0132	18	PA		6-4	33-22-21	D11974		2		GD08012	AC..	1		YC051-YL999
	0133	18	PA		6-4	33-22-21	D11974		3		GD08012	ST..	1		YC051-YL999
	0134	24	PK		8-7	33-22-21	SM00034			S	D11974		4		YD158-YD170
	0134	24	PK		8-7	33-22-21	D11974		4		SM00034		S		YL951-YL999
	0135	24	PK		8-7	33-22-21	D11974		5		SM00035		S		YC051-YL999
	0136	24	PK		8-7	33-22-21	D11974		6		SM00036		S		YC051-YL999
	0141	18	PA		4-4	33-22-21	D11976		1		SM00031		S		YC051-YL999
	0142	18	PA		9-11	33-22-21	D11976		2		GD03742	AC..	1		YC051-YL999
	0143	18	PA		9-11	33-22-21	D11976		3		GD03742	ST..	1		YC051-YL999
	0145	24	PK		4-4	33-22-21	D11976		5		SM00035		S		YC051-YL999
	0146	24	PK		4-4	33-22-21	D11976		6		SM00036		S		YC051-YL999
	0171	18	PA		14-5	33-22-22	D11986		1		SM00061		S		YC051-YL999
	0172	18	PA		3-3	33-22-22	D11986		2		GD08028	AC..	1		YC051-YL999
	0173	18	PA		3-3	33-22-22	D11986		3		GD08028	ST..	1		YC051-YL999
	0174	24	PK		22-11	33-22-22	D11986		4		SM00044		S		YD158-YL999
	0175	24	PK		3-11	33-22-22	D11986		5		SM00075		S		YC051-YL999
	0176	24	PK		3-11	33-22-22	D11986		6		SM00076		S		YC051-YL999
	0301	18	PA		4-1	33-22-21	D40110J		1		SM00001		S		YC051-YN260
	0310	20	PA		4-9	33-51-14	D40038P		10		D07186P	= 1	VR		YD158-YL999
	0310	20	PA		5-5	33-51-14	D40038P		10		D07186P	= 1	VR		YN231-YN260
	0311	20	PA		5-3	33-51-14	D40038P		11		GD03770	DC..	1		YD158-YL999
	0311	20	PA		6-0	33-51-14	D40038P		11		GD03770	DC..	1		YN231-YN260
	0321	18	PA		8-8	33-22-21	SM00001			S	SM00021		S		YC051-YL999
	0321	18	PA		7-11	33-22-21	SM00001			S	SM00021		S		YN231-YN260
	0331	18	PA		12-2	33-22-21	SM00021			S	SM00031		S		YC051-YD157, YL951-YL999
	0331	18	PA		13-2	33-22-21	D42010J		1		SM00031		S		YD158-YD170
	0341	18	PA		3-9	33-22-21	D40112J		1		SM00041		S		YC051-YD157, YL951-YL999

WIRE LIST

D280A108

91-21-11

Section W3140

Page 29

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3146	286A3146				FLUORESCENT LIGHTING - CEILING LEFT & RIGHT (continued)										
0341	18		PA		16-7	33-22-21	SM00031		S		SM00041		S		YD158-YD170
0341	18		PA		4-3	33-22-21	D40112J		1		SM00041		S		YN231-YN260
0361	18		PA		9-7	33-22-22	SM00041		S		SM00061		S		YC051-YD157, YL951-YL999
0361	18		PA		8-3	33-22-22	D40984J		1		SM00061		S		YD158-YD170
0361	18		PA		14-10	33-22-22	SM00041		S		SM00061		S		YN231-YN260
0381	18		PA		7-7	33-22-22	D40114J		1		SM00081		S		YC051-YD157, YL951-YL999
0381	18		PA		2-1	33-22-22	D40994J		1		SM00081		S		YD158-YD170
0381	18		PA		8-1	33-22-22	D40114J		1		SM00081		S		YN231-YN260
0383	18		PA		55-11	SPARE	D42010J		2		D40994J		3		YD158-YD170
0401	20		PA		76-9	SPARE	D40052J		1		D40038P		CAP	Y	YC051-YL999
0401	20		PA		57-6	SPARE	D40052J		1		D40038P		CAP	Y	YN231-YN260
0402	20		PA		76-9	SPARE	D40052J		2		D40038P		CAP	Y	YC051-YL999
0402	20		PA		57-6	SPARE	D40052J		2		D40038P		CAP	Y	YN231-YN260
0403	24		PK		12-3	33-22-21	D40052J		3		SM00024		S		YC051-YD157
0403	24		PK		4-2	33-22-21	D40052J		3		SM00004		S		YD158-YD170
0403	24		PK		12-3	33-22-21	D40052J		3		SM00004		S		YL951-YL999
0403	24		PK		4-4	33-22-21	D40052J		3		SM00004		S		YN231-YN260
0405	24		PK		4-2	33-22-21	D40052J		5		SM00005		S		YC051-YL999
0405	24		PK		4-4	33-22-21	D40052J		5		SM00005		S		YN231-YN260
0406	24		PK		4-2	33-22-21	D40052J		6		SM00006		S		YC051-YL999
0406	24		PK		4-4	33-22-21	D40052J		6		SM00006		S		YN231-YN260
0425	24		PK		8-8	33-22-21	SM00005		S		SM00025		S		YC051-YL999
0425	24		PK		7-11	33-22-21	SM00005		S		SM00025		S		YN231-YN260
0426	24		PK		8-8	33-22-21	SM00006		S		SM00026		S		YC051-YL999
0426	24		PK		7-11	33-22-21	SM00006		S		SM00026		S		YN231-YN260
0434	24		PK		19-9	33-22-21	SM00004		S		SM00034		S		YD158-YD170
0434	24		PK		12-2	33-22-21	SM00004		S		SM00034		S		YL951-YL999
0435	24		PK		12-2	33-22-21	SM00025		S		SM00035		S		YC051-YL999
0436	24		PK		12-2	33-22-21	SM00026		S		SM00036		S		YC051-YL999
0444	24		PK		27-8	33-22-21	SM00024		S		SM00044		S		YC051-YD157
0444	24		PK		16-7	33-22-21	SM00034		S		SM00044		S		YD158-YL999
0444	24		PK		19-9	33-22-21	SM00004		S		SM00044		S		YN231-YN260
0445	24		PK		16-7	33-22-21	SM00035		S		SM00045		S		YC051-YL999
0445	24		PK		12-11	33-22-21	SM00025		S		SM00045		S		YN231-YN260
0446	24		PK		16-7	33-22-21	SM00036		S		SM00046		S		YC051-YL999
0446	24		PK		12-11	33-22-21	SM00026		S		SM00046		S		YN231-YN260
0464	24		PK		9-7	33-22-22	SM00044		S		SM00064		S		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W3140

Page 30

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3146		286A3146			FLUORESCENT LIGHTING - CEILING LEFT & RIGHT (continued)											
0465		24		PK		9-7	33-22-22	SM00045		S		SM00065		S		YC051-YL999
0465		24		PK		14-10	33-22-22	SM00045		S		SM00065		S		YN231-YN260
0466		24		PK		9-7	33-22-22	SM00046		S		SM00066		S		YC051-YL999
0466		24		PK		14-10	33-22-22	SM00046		S		SM00066		S		YN231-YN260
0475		24		PK		13-7	33-22-22	SM00065		S		SM00075		S		YC051-YL999
0476		24		PK		13-7	33-22-22	SM00066		S		SM00076		S		YC051-YL999
0485		24		PK		7-3	33-22-22	SM00075		S		SM00085		S		YC051-YL999
0485		24		PK		10-10	33-22-22	SM00065		S		SM00085		S		YN231-YN260
0486		24		PK		7-3	33-22-22	SM00076		S		SM00086		S		YC051-YL999
0486		24		PK		10-10	33-22-22	SM00066		S		SM00086		S		YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W3140

Page 31 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S										
0001	16		CQ		5-2	35-21-21	D07176J	= 1	VS		SM00409		S		YC051-YL999, YR301-YR328
0001	16		CQ		1-7	35-21-21	D07176J	= 1	VS		SM00409		S		YN231-YN501
0101WY	18		PA		2-7	33-25-21	SM00501		S		SM00521		S		YC051-YL999, YR301-YR328
0101WY	18		PA		3-9	33-25-21	SM00501		S		SM00521		S		YN231-YN501
0102WV	22		PA		2-7	33-27-21	SM00502		S		SM00522		S		YC051-YL999, YR301-YR328
0102WV	22		PA		3-9	33-27-21	SM00502		S		SM00522		S		YN231-YN501
0103WG	22		PA		2-7	33-27-21	SM00503		S		SM00523		S		YC051-YL999, YR301-YR328
0103WG	22		PA		3-9	33-27-21	SM00503		S		SM00523		S		YN231-YN501
0104WO	22		PA		2-7	33-27-21	SM00504		S		SM00524		S		YC051-YL999, YR301-YR328
0104WO	22		PA		3-9	33-27-21	SM00504		S		SM00524		S		YN231-YN501
0105V	22		PA		2-7	33-27-21	SM00505		S		SM00525		S		YC051-YL999, YR301-YR328
0105V	22		PA		3-9	33-27-21	SM00505		S		SM00525		S		YN231-YN501
0106N	18		PA		2-7	33-23-11	SM00506		S		SM00526		S		YC051-YL999, YR301-YR328
0106N	18		PA		3-9	33-23-11	SM00506		S		SM00526		S		YN231-YN501
0107W	20		PA		2-7	33-25-21	SM00507		S		SM00527		S		YC051-YL999, YR301-YR328
0107W	20		PA		3-9	33-25-21	SM00507		S		SM00527		S		YN231-YN501
0108O	18		PA		2-7	33-23-11	SM00508		S		SM00528		S		YC051-YL999, YR301-YR328
0108O	18		PA		3-9	33-23-11	SM00508		S		SM00528		S		YN231-YN501
0109A	16		CQ		2-7	35-21-21	SM00509		S		SM00529		S		YC051-YL999, YR301-YR328
0109A	16		CQ		3-9	35-21-21	SM00509		S		SM00529		S		YN231-YN501
0110K	18		PA		2-7	33-27-21	SM00510		S		SM00530		S		YC051-YL999, YR301-YR328
0110K	18		PA		3-9	33-27-21	SM00510		S		SM00530		S		YN231-YN501
0121WY	18		PA		3-9	33-25-21	SM00521		S		SM00541		S		YC051-YL999, YR301-YR328
0121WY	18		PA		3-10	33-25-21	SM00521		S		SM00541		S		YN231-YN501
0122WV	22		PA		3-9	33-27-21	SM00522		S		SM00542		S		YC051-YL999, YR301-YR328
0122WV	22		PA		3-10	33-27-21	SM00522		S		SM00542		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
0123WG	22		PA		3-9	33-27-21		SM00523		S		SM00543		S	YC051-YL999, YR301-YR328
0123WG	22		PA		3-10	33-27-21		SM00523		S		SM00543		S	YN231-YN501
0124WO	22		PA		3-9	33-27-21		SM00524		S		SM00544		S	YC051-YL999, YR301-YR328
0124WO	22		PA		3-10	33-27-21		SM00524		S		SM00544		S	YN231-YN501
0125V	22		PA		3-9	33-27-21		SM00525		S		SM00545		S	YC051-YL999, YR301-YR328
0125V	22		PA		3-10	33-27-21		SM00525		S		SM00545		S	YN231-YN501
0126N	18		PA		3-9	33-23-11		SM00526		S		SM00546		S	YC051-YL999, YR301-YR328
0126N	18		PA		3-10	33-23-11		SM00526		S		SM00546		S	YN231-YN501
0127W	20		PA		3-9	33-25-21		SM00527		S		SM00547		S	YC051-YL999, YR301-YR328
0127W	20		PA		3-10	33-25-21		SM00527		S		SM00547		S	YN231-YN501
0128O	18		PA		3-9	33-23-11		SM00528		S		SM00548		S	YC051-YL999, YR301-YR328
0128O	18		PA		3-10	33-23-11		SM00528		S		SM00548		S	YN231-YN501
0129A	16		CQ		3-9	35-21-21		SM00529		S		SM00549		S	YC051-YL999, YR301-YR328
0129A	16		CQ		3-10	35-21-21		SM00529		S		SM00549		S	YN231-YN501
0130K	18		PA		3-9	33-27-21		SM00530		S		SM00550		S	YC051-YL999, YR301-YR328
0130K	18		PA		3-10	33-27-21		SM00530		S		SM00550		S	YN231-YN501
0141WY	18		PA		3-11	33-25-21		SM00541		S		SM00561		S	ALL
0142WV	22		PA		3-11	33-27-21		SM00542		S		SM00562		S	ALL
0143WG	22		PA		3-11	33-27-21		SM00543		S		SM00563		S	ALL
0144WO	22		PA		3-11	33-27-21		SM00544		S		SM00564		S	ALL
0145V	22		PA		3-11	33-27-21		SM00545		S		SM00565		S	ALL
0147W	20		PA		3-11	33-25-21		SM00547		S		SM00567		S	ALL
0149A	16		CQ		3-11	35-21-21		SM00549		S		SM00569		S	ALL
0150K	18		PA		3-11	33-27-21		SM00550		S		SM00570		S	ALL
0161WY	18		PA		6-4	33-25-21		SM00561		S		SM00581		S	YC051-YL999, YR301-YR328
0161WY	18		PA		2-3	33-25-21		SM00561		S		SM00581		S	YN231-YN501
0162WV	22		PA		6-4	33-27-21		SM00562		S		SM00582		S	YC051-YL999, YR301-YR328
0162WV	22		PA		2-3	33-27-21		SM00562		S		SM00582		S	YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
0163WG	22		PA		6-4	33-27-21	SM00563		S		SM00583		S		YC051-YL999, YR301-YR328
0163WG	22		PA		2-3	33-27-21	SM00563		S		SM00583		S		YN231-YN501
0164WO	22		PA		6-4	33-27-21	SM00564		S		SM00584		S		YC051-YL999, YR301-YR328
0164WO	22		PA		2-3	33-27-21	SM00564		S		SM00584		S		YN231-YN501
0165V	22		PA		6-4	33-27-21	SM00565		S		SM00585		S		YC051-YL999, YR301-YR328
0165V	22		PA		2-3	33-27-21	SM00565		S		SM00585		S		YN231-YN501
0166N	18		PA		6-4	33-23-11	SM00566		S		SM00586		S		YC051-YL999, YR301-YR328
0166N	18		PA		2-3	33-23-11	SM00566		S		SM00586		S		YN231-YN501
0167W	20		PA		6-4	33-25-21	SM00567		S		SM00587		S		YC051-YL999, YR301-YR328
0167W	20		PA		2-3	33-25-21	SM00567		S		SM00587		S		YN231-YN501
0168O	18		PA		6-4	33-23-11	SM00568		S		SM00588		S		YC051-YL999, YR301-YR328
0168O	18		PA		2-3	33-23-11	SM00568		S		SM00588		S		YN231-YN501
0169A	16		CQ		6-4	35-21-21	SM00569		S		SM00589		S		YC051-YL999, YR301-YR328
0169A	16		CQ		2-3	35-21-21	SM00569		S		SM00589		S		YN231-YN501
0170K	18		PA		6-4	33-27-21	SM00570		S		SM00590		S		YC051-YL999, YR301-YR328
0170K	18		PA		2-3	33-27-21	SM00570		S		SM00590		S		YN231-YN501
0181WY	18		PA		4-3	33-25-21	SM00581		S		SM00601		S		YC051-YL999, YR301-YR328
0181WY	18		PA		7-8	33-25-21	SM00581		S		SM00641		S		YN231-YN501
0182WV	22		PA		4-3	33-27-21	SM00582		S		SM00602		S		YC051-YL999, YR301-YR328
0182WV	22		PA		7-9	33-27-21	SM00582		S		SM00642		S		YN231-YN501
0183WG	22		PA		4-3	33-27-21	SM00583		S		SM00603		S		YC051-YL999, YR301-YR328
0183WG	22		PA		7-9	33-27-21	SM00583		S		SM00643		S		YN231-YN501
0184WO	22		PA		4-3	33-27-21	SM00584		S		SM00604		S		YC051-YL999, YR301-YR328
0184WO	22		PA		7-9	33-27-21	SM00584		S		SM00644		S		YN231-YN501
0185V	22		PA		4-3	33-27-21	SM00585		S		SM00605		S		YC051-YL999, YR301-YR328
0185V	22		PA		7-9	33-27-21	SM00585		S		SM00645		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W3150	286A3150			P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
0186N	18		PA	4-3	33-23-11	SM00586		S		SM00606		S		YC051-YL999, YR301-YR328
0187W	20		PA	4-3	33-25-21	SM00587		S		SM00607		S		YC051-YL999, YR301-YR328
0187W	20		PA	7-8	33-25-21	SM00587		S		SM00647		S		YN231-YN501
0188O	18		PA	4-3	33-23-11	SM00588		S		SM00608		S		YC051-YL999, YR301-YR328
0189A	16		CQ	4-3	35-21-21	SM00589		S		SM00609		S		YC051-YL999, YR301-YR328
0189A	16		CQ	7-9	35-21-21	SM00589		S		SM00649		S		YN231-YN501
0190K	18		PA	4-3	33-27-21	SM00590		S		SM00610		S		YC051-YL999, YR301-YR328
0190K	18		PA	7-9	33-27-21	SM00590		S		SM00650		S		YN231-YN501
0201WY	18		PA	4-3	33-25-21	SM00601		S		SM00621		S		YC051-YL999, YR301-YR328
0202WV	22		PA	4-3	33-27-21	SM00602		S		SM00622		S		YC051-YL999, YR301-YR328
0203WG	22		PA	4-3	33-27-21	SM00603		S		SM00623		S		YC051-YL999, YR301-YR328
0204WO	22		PA	4-3	33-27-21	SM00604		S		SM00624		S		YC051-YL999, YR301-YR328
0205V	22		PA	4-3	33-27-21	SM00605		S		SM00625		S		YC051-YL999, YR301-YR328
0207W	20		PA	4-3	33-25-21	SM00607		S		SM00627		S		YC051-YL999, YR301-YR328
0209A	16		CQ	4-3	35-21-21	SM00609		S		SM00629		S		YC051-YL999, YR301-YR328
0210K	18		PA	4-3	33-27-21	SM00610		S		SM00630		S		YC051-YL999, YR301-YR328
0221WY	18		PA	4-3	33-25-21	SM00621		S		SM00641		S		YC051-YL999, YR301-YR328
0222WV	22		PA	4-3	33-27-21	SM00622		S		SM00642		S		YC051-YL999, YR301-YR328
0223WG	22		PA	4-3	33-27-21	SM00623		S		SM00643		S		YC051-YL999, YR301-YR328
0224WO	22		PA	4-3	33-27-21	SM00624		S		SM00644		S		YC051-YL999, YR301-YR328
0225V	22		PA	4-3	33-27-21	SM00625		S		SM00645		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3150

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
0226N	18		PA		4-3	33-23-11	SM00626		S		SM00646		S		YC051-YL999, YR301-YR328
0227W	20		PA		4-3	33-25-21	SM00627		S		SM00647		S		YC051-YL999, YR301-YR328
0228O	18		PA		4-3	33-23-11	SM00628		S		SM00648		S		YC051-YL999, YR301-YR328
0229A	16		CQ		4-3	35-21-21	SM00629		S		SM00649		S		YC051-YL999, YR301-YR328
0230K	18		PA		4-3	33-27-21	SM00630		S		SM00650		S		YC051-YL999, YR301-YR328
0241WY	18		PA		6-3	33-25-21	SM00641		S		SM00661		S		YC051-YL999, YR301-YR328
0241WY	18		PA		9-4	33-25-21	SM00641		S		SM00661		S		YN231-YN501
0242WV	22		PA		6-3	33-27-21	SM00642		S		SM00662		S		YC051-YL999, YR301-YR328
0242WV	22		PA		9-4	33-27-21	SM00642		S		SM00662		S		YN231-YN501
0243WG	22		PA		6-3	33-27-21	SM00643		S		SM00663		S		YC051-YL999, YR301-YR328
0243WG	22		PA		9-4	33-27-21	SM00643		S		SM00663		S		YN231-YN501
0244WO	22		PA		6-3	33-27-21	SM00644		S		SM00664		S		YC051-YL999, YR301-YR328
0244WO	22		PA		9-4	33-27-21	SM00644		S		SM00664		S		YN231-YN501
0245V	22		PA		6-3	33-27-21	SM00645		S		SM00665		S		YC051-YL999, YR301-YR328
0245V	22		PA		9-4	33-27-21	SM00645		S		SM00665		S		YN231-YN501
0246N	18		PA		6-3	33-23-11	SM00646		S		SM00666		S		YC051-YL999, YR301-YR328
0247W	20		PA		6-3	33-25-21	SM00647		S		SM00667		S		YC051-YL999, YR301-YR328
0247W	20		PA		9-4	33-25-21	SM00647		S		SM00667		S		YN231-YN501
0248O	18		PA		6-3	33-23-11	SM00648		S		SM00668		S		YC051-YL999, YR301-YR328
0249A	16		CQ		6-3	35-21-21	SM00649		S		SM00669		S		YC051-YL999, YR301-YR328
0249A	16		CQ		9-4	35-21-21	SM00649		S		SM00669		S		YN231-YN501
0250K	18		PA		6-3	33-27-21	SM00650		S		SM00670		S		YC051-YL999, YR301-YR328
0250K	18		PA		9-4	33-27-21	SM00650		S		SM00670		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 5

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
0261WY	18		PA		3-9	33-25-21	SM00661			S		SM00681		S		YC051-YL999, YR301-YR328
0261WY	18		PA		4-4	33-25-21	SM00661			S		SM00681		S		YN231-YN501
0262WV	22		PA		3-9	33-27-21	SM00662			S		SM00682		S		YC051-YL999, YR301-YR328
0262WV	22		PA		4-4	33-27-22	SM00662			S		SM00682		S		YN231-YN501
0263WG	22		PA		3-9	33-27-21	SM00663			S		SM00683		S		YC051-YL999, YR301-YR328
0263WG	22		PA		4-4	33-27-22	SM00663			S		SM00683		S		YN231-YN501
0264WO	22		PA		3-9	33-27-21	SM00664			S		SM00684		S		YC051-YL999, YR301-YR328
0264WO	22		PA		4-4	33-27-22	SM00664			S		SM00684		S		YN231-YN501
0265V	22		PA		3-9	33-27-21	SM00665			S		SM00685		S		YC051-YL999, YR301-YR328
0265V	22		PA		4-4	33-27-22	SM00665			S		SM00685		S		YN231-YN501
0266N	18		PA		4-4	33-23-11	SM00666			S		SM00686		S		YN231-YN501
0267W	20		PA		3-9	33-25-21	SM00667			S		SM00687		S		YC051-YL999, YR301-YR328
0267W	20		PA		4-4	33-25-21	SM00667			S		SM00687		S		YN231-YN501
0268O	18		PA		4-4	33-23-11	SM00668			S		SM00688		S		YN231-YN501
0269A	16		CQ		3-9	35-21-21	SM00669			S		SM00689		S		YC051-YL999, YR301-YR328
0269A	16		CQ		4-4	35-21-21	SM00669			S		SM00689		S		YN231-YN501
0270K	18		PA		3-9	33-27-21	SM00670			S		SM00690		S		YC051-YL999, YR301-YR328
0270K	18		PA		4-4	33-27-22	SM00670			S		SM00690		S		YN231-YN501
0281WY	18		PA		3-9	33-25-21	SM00681			S		SM00701		S		YC051-YL999, YR301-YR328
0282WV	22		PA		3-9	33-27-21	SM00682			S		SM00702		S		YC051-YL999, YR301-YR328
0282WV	22		PA		3-7	33-27-22	SM00682			S		SM00702		S		YN231-YN501
0283WG	22		PA		3-9	33-27-21	SM00683			S		SM00703		S		YC051-YL999, YR301-YR328
0283WG	22		PA		3-7	33-27-22	SM00683			S		SM00703		S		YN231-YN501
0284WO	22		PA		3-9	33-27-21	SM00684			S		SM00704		S		YC051-YL999, YR301-YR328
0284WO	22		PA		3-7	33-27-22	SM00684			S		SM00704		S		YN231-YN501
0285V	22		PA		3-9	33-27-21	SM00685			S		SM00705		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3150

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
0285V	22		PA		3-7	33-27-22	SM00685				SM00705		S		YN231-YN501
0286N	18		PA		3-9	33-23-11	SM00686				SM00706		S		YC051-YL999, YR301-YR328
0287W	20		PA		3-9	33-25-21	SM00687				SM00707		S		YC051-YL999, YR301-YR328
0288O	18		PA		3-9	33-23-11	SM00688				SM00708		S		YC051-YL999, YR301-YR328
0289A	16		CQ		3-9	35-21-21	SM00689				SM00709		S		YC051-YL999, YR301-YR328
0290K	18		PA		3-9	33-27-21	SM00690				SM00710		S		YC051-YL999, YR301-YR328
0290K	18		PA		3-7	33-27-22	SM00690				SM00710		S		YN231-YN501
0301WY	18		PA		2-5	33-25-21	SM00701				SM00721		S		YC051-YL999, YR301-YR328
0301WY	18		PA		8-2	33-25-22	SM00701				SM00721		S		YN231-YN501
0302WV	22		PA		2-5	33-27-21	SM00702				SM00722		S		YC051-YL999, YR301-YR328
0302WV	22		PA		8-2	33-27-22	SM00702				SM00722		S		YN231-YN501
0303WG	22		PA		2-5	33-27-21	SM00703				SM00723		S		YC051-YL999, YR301-YR328
0303WG	22		PA		8-2	33-27-22	SM00703				SM00723		S		YN231-YN501
0304WO	22		PA		2-5	33-27-21	SM00704				SM00724		S		YC051-YL999, YR301-YR328
0304WO	22		PA		8-2	33-27-22	SM00704				SM00724		S		YN231-YN501
0305V	22		PA		2-5	33-27-21	SM00705				SM00725		S		YC051-YL999, YR301-YR328
0305V	22		PA		8-2	33-27-22	SM00705				SM00725		S		YN231-YN501
0306N	18		PA		2-5	33-23-11	SM00706				SM00726		S		YC051-YL999, YR301-YR328
0306N	18		PA		8-2	33-23-12	SM00706				SM00726		S		YN231-YN501
0307W	20		PA		2-5	33-25-21	SM00707				SM00727		S		YC051-YL999, YR301-YR328
0307W	20		PA		8-2	33-25-22	SM00707				SM00727		S		YN231-YN501
0308O	18		PA		2-5	33-23-11	SM00708				SM00728		S		YC051-YL999, YR301-YR328
0308O	18		PA		8-2	33-23-12	SM00708				SM00728		S		YN231-YN501
0309A	16		CQ		2-5	35-21-21	SM00709				SM00729		S		YC051-YL999, YR301-YR328
0309A	16		CQ		8-2	35-21-21	SM00709				SM00729		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 7

Nov 12/2012

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150			P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
0310K	18		PA		2-5	33-27-21	SM00710		S		SM00730		S		YC051-YL999, YR301-YR328
0310K	18		PA		8-2	33-27-22	SM00710		S		SM00730		S		YN231-YN501
0321WY	18		PA		4-0	33-25-22	SM00721		S		SM00741		S		YN231-YN501
0322WV	22		PA		6-8	33-27-22	SM00722		S		SM00742		S		YC051-YL999, YR301-YR328
0322WV	22		PA		4-0	33-27-22	SM00722		S		SM00742		S		YN231-YN501
0323WG	22		PA		6-8	33-27-22	SM00723		S		SM00743		S		YC051-YL999, YR301-YR328
0323WG	22		PA		4-0	33-27-22	SM00723		S		SM00743		S		YN231-YN501
0324WO	22		PA		6-8	33-27-22	SM00724		S		SM00744		S		YC051-YL999, YR301-YR328
0324WO	22		PA		4-0	33-27-22	SM00724		S		SM00744		S		YN231-YN501
0325V	22		PA		6-8	33-27-22	SM00725		S		SM00745		S		YC051-YL999, YR301-YR328
0325V	22		PA		4-0	33-27-22	SM00725		S		SM00745		S		YN231-YN501
0327W	20		PA		4-0	33-25-22	SM00727		S		SM00747		S		YN231-YN501
0329A	16		CQ		4-0	35-21-21	SM00729		S		SM00749		S		YN231-YN501
0330K	18		PA		6-8	33-27-22	SM00730		S		SM00750		S		YC051-YL999, YR301-YR328
0330K	18		PA		4-0	33-27-22	SM00730		S		SM00750		S		YN231-YN501
0341WY	18		PA		4-0	33-25-22	SM00741		S		SM00761		S		YC051-YL999, YR301-YR328
0341WY	18		PA		3-6	33-25-22	SM00741		S		SM00821		S		YN231-YN501
0342WV	22		PA		4-0	33-27-22	SM00742		S		SM00762		S		YC051-YL999, YR301-YR328
0342WV	22		PA		3-6	33-27-22	SM00742		S		SM00822		S		YN231-YN501
0343WG	22		PA		4-0	33-27-22	SM00743		S		SM00763		S		YC051-YL999, YR301-YR328
0343WG	22		PA		3-6	33-27-22	SM00743		S		SM00823		S		YN231-YN501
0344WO	22		PA		4-0	33-27-22	SM00744		S		SM00764		S		YC051-YL999, YR301-YR328
0344WO	22		PA		3-6	33-27-22	SM00744		S		SM00824		S		YN231-YN501
0345V	22		PA		4-0	33-27-22	SM00745		S		SM00765		S		YC051-YL999, YR301-YR328
0345V	22		PA		3-6	33-27-22	SM00745		S		SM00825		S		YN231-YN501
0346N	18		PA		4-0	33-23-12	SM00746		S		SM00766		S		YC051-YL999, YR301-YR328
0346N	18		PA		3-6	33-23-12	SM00746		S		SM00826		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity			
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice	
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
0347W	20		PA		4-0	33-25-22	SM00747		S		SM00767		S		YC051-YL999, YR301-YR328	
0347W	20		PA		3-6	33-25-22	SM00747		S		SM00827		S		YN231-YN501	
0348O	18		PA		4-0	33-23-12	SM00748		S		SM00768		S		YC051-YL999, YR301-YR328	
0348O	18		PA		3-6	33-23-12	SM00748		S		SM00828		S		YN231-YN501	
0349A	16		CQ		4-0	35-21-21	SM00749		S		SM00769		S		YC051-YL999, YR301-YR328	
0349A	16		CQ		3-6	35-21-21	SM00749		S		SM00829		S		YN231-YN501	
0350K	18		PA		4-0	33-27-22	SM00750		S		SM00770		S		YC051-YL999, YR301-YR328	
0350K	18		PA		3-6	33-27-22	SM00750		S		SM00830		S		YN231-YN501	
0361WY	18		PA		2-7	33-25-22	SM00761		S		SM00781		S		YC051-YL999, YR301-YR328	
0362WV	22		PA		2-7	33-27-22	SM00762		S		SM00782		S		YC051-YL999, YR301-YR328	
0363WG	22		PA		2-7	33-27-22	SM00763		S		SM00783		S		YC051-YL999, YR301-YR328	
0364WO	22		PA		2-7	33-27-22	SM00764		S		SM00784		S		YC051-YL999, YR301-YR328	
0365V	22		PA		2-7	33-27-22	SM00765		S		SM00785		S		YC051-YL999, YR301-YR328	
0366N	18		PA		2-7	33-23-12	SM00766		S		SM00786		S		YC051-YL999, YR301-YR328	
0367W	20		PA		2-7	33-25-22	SM00767		S		SM00787		S		YC051-YL999, YR301-YR328	
0368O	18		PA		2-7	33-23-12	SM00768		S		SM00788		S		YC051-YL999, YR301-YR328	
0369A	16		CQ		2-7	35-21-21	SM00769		S		SM00789		S		YC051-YL999, YR301-YR328	
0370K	18		PA		2-7	33-27-22	SM00770		S		SM00790		S		YC051-YL999, YR301-YR328	
0381WY	18		PA		3-9	33-25-22	SM00781		S		SM00801		S		YC051-YL999, YR301-YR328	
0382WV	22		PA		3-9	33-27-22	SM00782		S		SM00802		S		YC051-YL999, YR301-YR328	
0383WG	22		PA		3-9	33-27-22	SM00783		S		SM00803		S		YC051-YL999, YR301-YR328	

WIRE LIST

D280A108

91-21-11

Section W3150

Page 9

Nov 12/2012

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150			P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
0384WO	22		PA		3-9	33-27-22	SM00784		S		SM00804		S		YC051-YL999, YR301-YR328
0385V	22		PA		3-9	33-27-22	SM00785		S		SM00805		S		YC051-YL999, YR301-YR328
0387W	20		PA		3-9	33-25-22	SM00787		S		SM00807		S		YC051-YL999, YR301-YR328
0389A	16		CQ		3-9	35-21-21	SM00789		S		SM00809		S		YC051-YL999, YR301-YR328
0390K	18		PA		3-9	33-27-22	SM00790		S		SM00810		S		YC051-YL999, YR301-YR328
0401WY	18		PA		4-3	33-25-22	SM00801		S		SM00821		S		YC051-YL999, YR301-YR328
0402WV	22		PA		4-3	33-27-22	SM00802		S		SM00822		S		YC051-YL999, YR301-YR328
0403WG	22		PA		4-3	33-27-22	SM00803		S		SM00823		S		YC051-YL999, YR301-YR328
0404WO	22		PA		4-3	33-27-22	SM00804		S		SM00824		S		YC051-YL999, YR301-YR328
0405V	22		PA		4-3	33-27-22	SM00805		S		SM00825		S		YC051-YL999, YR301-YR328
0406N	18		PA		4-3	33-23-12	SM00806		S		SM00826		S		YC051-YL999, YR301-YR328
0407W	20		PA		4-3	33-25-22	SM00807		S		SM00827		S		YC051-YL999, YR301-YR328
0408O	18		PA		4-3	33-23-12	SM00808		S		SM00828		S		YC051-YL999, YR301-YR328
0409A	16		CQ		4-3	35-21-21	SM00809		S		SM00829		S		YC051-YL999, YR301-YR328
0410K	18		PA		4-3	33-27-22	SM00810		S		SM00830		S		YC051-YL999, YR301-YR328
0421WY	18		PA		4-3	33-25-22	SM00821		S		SM00841		S		YC051-YL999, YR301-YR328
0421WY	18		PA		8-1	33-25-22	SM00821		S		SM00841		S		YN231-YN501
0422WV	22		PA		4-3	33-27-22	SM00822		S		SM00842		S		YC051-YL999, YR301-YR328
0422WV	22		PA		8-1	33-27-22	SM00822		S		SM00842		S		YN231-YN501
0423WG	22		PA		4-3	33-27-22	SM00823		S		SM00843		S		YC051-YL999, YR301-YR328
0423WG	22		PA		8-1	33-27-22	SM00823		S		SM00843		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
0424WO	22		PA		4-3	33-27-22	SM00824		S		SM00844		S		YC051-YL999, YR301-YR328
0424WO	22		PA		8-1	33-27-22	SM00824		S		SM00844		S		YN231-YN501
0425V	22		PA		4-3	33-27-22	SM00825		S		SM00845		S		YC051-YL999, YR301-YR328
0425V	22		PA		8-1	33-27-22	SM00825		S		SM00845		S		YN231-YN501
0427W	20		PA		4-3	33-25-22	SM00827		S		SM00847		S		YC051-YL999, YR301-YR328
0427W	20		PA		8-1	33-25-22	SM00827		S		SM00847		S		YN231-YN501
0429A	16		CQ		4-3	35-21-21	SM00829		S		SM00849		S		YC051-YL999, YR301-YR328
0429A	16		CQ		8-1	35-21-21	SM00829		S		SM00849		S		YN231-YN501
0430K	18		PA		4-3	33-27-22	SM00830		S		SM00850		S		YC051-YL999, YR301-YR328
0430K	18		PA		8-1	33-27-22	SM00830		S		SM00850		S		YN231-YN501
0441WY	18		PA		4-1	33-25-22	SM00841		S		SM00861		S		YC051-YL999, YR301-YR328
0441WY	18		PA		5-4	33-25-22	SM00841		S		SM00861		S		YN231-YN501
0442WV	22		PA		4-1	33-27-22	SM00842		S		SM00862		S		YC051-YL999, YR301-YR328
0442WV	22		PA		5-4	33-27-22	SM00842		S		SM00862		S		YN231-YN501
0443WG	22		PA		4-1	33-27-22	SM00843		S		SM00863		S		YC051-YL999, YR301-YR328
0443WG	22		PA		5-4	33-27-22	SM00843		S		SM00863		S		YN231-YN501
0444WO	22		PA		4-1	33-27-22	SM00844		S		SM00864		S		YC051-YL999, YR301-YR328
0444WO	22		PA		5-4	33-27-22	SM00844		S		SM00864		S		YN231-YN501
0445V	22		PA		4-1	33-27-22	SM00845		S		SM00865		S		YC051-YL999, YR301-YR328
0445V	22		PA		5-4	33-27-22	SM00845		S		SM00865		S		YN231-YN501
0446N	18		PA		4-1	33-23-12	SM00846		S		SM00866		S		YC051-YL999, YR301-YR328
0446N	18		PA		5-4	33-23-12	SM00846		S		SM00866		S		YN231-YN501
0447W	20		PA		4-1	33-25-22	SM00847		S		SM00867		S		YC051-YL999, YR301-YR328
0447W	20		PA		5-4	33-25-22	SM00847		S		SM00867		S		YN231-YN501
0448O	18		PA		4-1	33-23-12	SM00848		S		SM00868		S		YC051-YL999, YR301-YR328
0448O	18		PA		5-4	33-23-12	SM00848		S		SM00868		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)												
0449A	16		CQ		4-1	35-21-21		SM00849		S		SM00869		S		YC051-YL999, YR301-YR328	
0449A	16		CQ		5-4	35-21-21		SM00849		S		SM00869		S		YN231-YN501	
0450K	18		PA		4-1	33-27-22		SM00850		S		SM00870		S		YC051-YL999, YR301-YR328	
0450K	18		PA		5-4	33-27-22		SM00850		S		SM00870		S		YN231-YN501	
0461WY	18		PA		4-2	33-25-22		SM00861		S		SM00881		S		YC051-YL999, YR301-YR328	
0462WV	22		PA		4-2	33-27-22		SM00862		S		SM00882		S		YC051-YL999, YR301-YR328	
0463WG	22		PA		4-2	33-27-22		SM00863		S		SM00883		S		YC051-YL999, YR301-YR328	
0464WO	22		PA		4-2	33-27-22		SM00864		S		SM00884		S		YC051-YL999, YR301-YR328	
0465V	22		PA		4-2	33-27-22		SM00865		S		SM00885		S		YC051-YL999, YR301-YR328	
0467W	20		PA		4-2	33-25-22		SM00867		S		SM00887		S		YC051-YL999, YR301-YR328	
0469A	16		CQ		4-2	35-21-21		SM00869		S		SM00889		S		YC051-YL999, YR301-YR328	
0470K	18		PA		4-2	33-27-22		SM00870		S		SM00890		S		YC051-YL999, YR301-YR328	
0481WY	18		PA		3-11	33-25-22		SM00881		S		SM00901		S		YC051-YL999, YR301-YR328	
0482WV	22		PA		3-11	33-27-22		SM00882		S		SM00902		S		YC051-YL999, YR301-YR328	
0483WG	22		PA		3-11	33-27-22		SM00883		S		SM00903		S		YC051-YL999, YR301-YR328	
0484WO	22		PA		3-11	33-27-22		SM00884		S		SM00904		S		YC051-YL999, YR301-YR328	
0485V	22		PA		3-11	33-27-22		SM00885		S		SM00905		S		YC051-YL999, YR301-YR328	
0486N	18		PA		3-11	33-23-12		SM00886		S		SM00906		S		YC051-YL999, YR301-YR328	
0487W	20		PA		3-11	33-25-22		SM00887		S		SM00907		S		YC051-YL999, YR301-YR328	
0488O	18		PA		3-11	33-23-12		SM00888		S		SM00908		S		YC051-YL999, YR301-YR328	

WIRE LIST

D280A108

91-21-11

Section W3150

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)												
0489A	16		CQ		3-11		35-21-21	SM00889		S		SM00909		S		YC051-YL999, YR301-YR328	
0490K	18		PA		3-11		33-27-22	SM00890		S		SM00910		S		YC051-YL999, YR301-YR328	
0491WY	18		PA		7-7		33-25-21	D11500		1		SM00501		S		YC051-YL999, YR301-YR328	
0491WY	18		PA		6-2		33-25-21	D11500		1		SM00501		S		YN231-YN501	
0492WV	22		PA		7-7		33-27-21	D11500		2		SM00502		S		YC051-YL999, YR301-YR328	
0492WV	22		PA		6-4		33-27-21	D11500		2		SM00502		S		YN231-YN501	
0493WG	22		PA		7-7		33-27-21	D11500		3		SM00503		S		YC051-YL999, YR301-YR328	
0493WG	22		PA		6-4		33-27-21	D11500		3		SM00503		S		YN231-YN501	
0494WO	22		PA		7-7		33-27-21	D11500		4		SM00504		S		YC051-YL999, YR301-YR328	
0494WO	22		PA		6-4		33-27-21	D11500		4		SM00504		S		YN231-YN501	
0495V	22		PA		7-7		33-27-21	D11500		5		SM00505		S		YC051-YL999, YR301-YR328	
0495V	22		PA		6-4		33-27-21	D11500		5		SM00505		S		YN231-YN501	
0496N	18		PA		7-7		33-23-11	D11500		6		SM00506		S		YC051-YL999, YR301-YR328	
0496N	18		PA		6-2		33-23-11	D11500		6		SM00506		S		YN231-YN501	
0497W	20		PA		7-7		33-25-21	D11500		7		SM00507		S		YC051-YL999, YR301-YR328	
0497W	20		PA		6-2		33-25-21	D11500		7		SM00507		S		YN231-YN501	
0498O	18		PA		7-7		33-23-11	D11500		8		SM00508		S		YC051-YL999, YR301-YR328	
0498O	18		PA		6-2		33-23-11	D11500		8		SM00508		S		YN231-YN501	
0499A	16		CQ		7-7		35-21-21	D11500		11		SM00509		S		YC051-YL999, YR301-YR328	
0499A	16		CQ		6-4		35-21-21	D11500		11		SM00509		S		YN231-YN501	
0500K	18		PA		7-7		33-27-21	D11500		10		SM00510		S		YC051-YL999, YR301-YR328	
0500K	18		PA		6-4		33-27-21	D11500		10		SM00510		S		YN231-YN501	
0501WY	18		PA		8-10		33-25-21	D11502		1		SM00501		S		YC051-YL999, YR301-YR328	
0501WY	18		PA		7-0		33-25-21	D11502		1		SM00501		S		YN231-YN501	
0502WV	22		PA		8-10		33-27-21	D11502		2		SM00502		S		YC051-YL999, YR301-YR328	

WIRE LIST

D280A108

91-21-11

Section W3150

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
0502WV	22		PA		7-1	33-27-21		D11502		2		SM00502		S		YN231-YN501
0503WG	22		PA		8-10	33-27-21		D11502		3		SM00503		S		YC051-YL999, YR301-YR328
0503WG	22		PA		7-1	33-27-21		D11502		3		SM00503		S		YN231-YN501
0504WO	22		PA		8-10	33-27-21		D11502		4		SM00504		S		YC051-YL999, YR301-YR328
0504WO	22		PA		7-1	33-27-21		D11502		4		SM00504		S		YN231-YN501
0505V	22		PA		8-10	33-27-21		D11502		5		SM00505		S		YC051-YL999, YR301-YR328
0505V	22		PA		7-1	33-27-21		D11502		5		SM00505		S		YN231-YN501
0506N	18		PA		8-10	33-23-11		D11502		6		SM00506		S		YC051-YL999, YR301-YR328
0506N	18		PA		7-0	33-23-11		D11502		6		SM00506		S		YN231-YN501
0507W	20		PA		8-10	33-25-21		D11502		7		SM00507		S		YC051-YL999, YR301-YR328
0507W	20		PA		7-0	33-25-21		D11502		7		SM00507		S		YN231-YN501
0508O	18		PA		8-10	33-23-11		D11502		8		SM00508		S		YC051-YL999, YR301-YR328
0508O	18		PA		7-0	33-23-11		D11502		8		SM00508		S		YN231-YN501
0509A	16		CQ		8-10	35-21-21		D11502		11		SM00509		S		YC051-YL999, YR301-YR328
0509A	16		CQ		7-1	35-21-21		D11502		11		SM00509		S		YN231-YN501
0510K	18		PA		8-10	33-27-21		D11502		10		SM00510		S		YC051-YL999, YR301-YR328
0510K	18		PA		7-1	33-27-21		D11502		10		SM00510		S		YN231-YN501
0511WY	18		PA		9-1	33-25-21		D11504		1		SM00521		S		YC051-YL999, YR301-YR328
0511WY	18		PA		7-5	33-25-21		D11504		1		SM00521		S		YN231-YN501
0512WV	22		PA		9-1	33-27-21		D11504		2		SM00522		S		YC051-YL999, YR301-YR328
0512WV	22		PA		7-2	33-27-21		D11504		2		SM00522		S		YN231-YN501
0513WG	22		PA		9-1	33-27-21		D11504		3		SM00523		S		YC051-YL999, YR301-YR328
0513WG	22		PA		7-2	33-27-21		D11504		3		SM00523		S		YN231-YN501
0514WO	22		PA		9-1	33-27-21		D11504		4		SM00524		S		YC051-YL999, YR301-YR328
0514WO	22		PA		7-2	33-27-21		D11504		4		SM00524		S		YN231-YN501
0515V	22		PA		9-1	33-27-21		D11504		5		SM00525		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3150

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
0515V	22		PA		7-2	33-27-21	D11504				SM00525		S		YN231-YN501
0516N	18		PA		9-1	33-23-11	D11504				SM00526		S		YC051-YL999, YR301-YR328
0516N	18		PA		7-5	33-23-11	D11504				SM00526		S		YN231-YN501
0517W	20		PA		9-1	33-25-21	D11504				SM00527		S		YC051-YL999, YR301-YR328
0517W	20		PA		7-5	33-25-21	D11504				SM00527		S		YN231-YN501
0518O	18		PA		9-1	33-23-11	D11504				SM00528		S		YC051-YL999, YR301-YR328
0518O	18		PA		7-5	33-23-11	D11504				SM00528		S		YN231-YN501
0519A	16		CQ		9-1	35-21-21	D11504				SM00529		S		YC051-YL999, YR301-YR328
0519A	16		CQ		7-2	35-21-21	D11504				SM00529		S		YN231-YN501
0520K	18		PA		9-1	33-27-21	D11504				SM00530		S		YC051-YL999, YR301-YR328
0520K	18		PA		7-2	33-27-21	D11504				SM00530		S		YN231-YN501
0521WY	18		PA		8-8	33-25-21	D11506				SM00521		S		YC051-YL999, YR301-YR328
0521WY	18		PA		7-8	33-25-21	D11506				SM00521		S		YN231-YN501
0522WV	22		PA		8-8	33-27-21	D11506				SM00522		S		YC051-YL999, YR301-YR328
0522WV	22		PA		7-3	33-27-21	D11506				SM00522		S		YN231-YN501
0523WG	22		PA		8-8	33-27-21	D11506				SM00523		S		YC051-YL999, YR301-YR328
0523WG	22		PA		7-3	33-27-21	D11506				SM00523		S		YN231-YN501
0524WO	22		PA		8-8	33-27-21	D11506				SM00524		S		YC051-YL999, YR301-YR328
0524WO	22		PA		7-3	33-27-21	D11506				SM00524		S		YN231-YN501
0525V	22		PA		8-8	33-27-21	D11506				SM00525		S		YC051-YL999, YR301-YR328
0525V	22		PA		7-3	33-27-21	D11506				SM00525		S		YN231-YN501
0526N	18		PA		8-8	33-23-11	D11506				SM00526		S		YC051-YL999, YR301-YR328
0526N	18		PA		7-8	33-23-11	D11506				SM00526		S		YN231-YN501
0527W	20		PA		8-8	33-25-21	D11506				SM00527		S		YC051-YL999, YR301-YR328
0527W	20		PA		7-8	33-25-21	D11506				SM00527		S		YN231-YN501
0528O	18		PA		8-8	33-23-11	D11506				SM00528		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11
Section W3150
Page 15
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
0528O	18		PA		7-8	33-23-11		D11506	8			SM00528		S		YN231-YN501
0529A	16		CQ		8-8	35-21-21		D11506	11			SM00529		S		YC051-YL999, YR301-YR328
0529A	16		CQ		7-3	35-21-21		D11506	11			SM00529		S		YN231-YN501
0530K	18		PA		8-8	33-27-21		D11506	10			SM00530		S		YC051-YL999, YR301-YR328
0530K	18		PA		7-3	33-27-21		D11506	10			SM00530		S		YN231-YN501
0531WY	18		PA		7-6	33-25-21		D11508	1			SM00541		S		YC051-YL999, YR301-YR328
0531WY	18		PA		7-5	33-25-21		D11508	1			SM00541		S		YN231-YN501
0532WV	22		PA		7-6	33-27-21		D11508	2			SM00542		S		YC051-YL999, YR301-YR328
0532WV	22		PA		7-4	33-27-21		D11508	2			SM00542		S		YN231-YN501
0533WG	22		PA		7-6	33-27-21		D11508	3			SM00543		S		YC051-YL999, YR301-YR328
0533WG	22		PA		7-4	33-27-21		D11508	3			SM00543		S		YN231-YN501
0534WO	22		PA		7-6	33-27-21		D11508	4			SM00544		S		YC051-YL999, YR301-YR328
0534WO	22		PA		7-4	33-27-21		D11508	4			SM00544		S		YN231-YN501
0535V	22		PA		7-6	33-27-21		D11508	5			SM00545		S		YC051-YL999, YR301-YR328
0535V	22		PA		7-4	33-27-21		D11508	5			SM00545		S		YN231-YN501
0536N	18		PA		7-6	33-23-11		D11508	6			SM00546		S		YC051-YL999, YR301-YR328
0536N	18		PA		7-5	33-23-11		D11508	6			SM00546		S		YN231-YN501
0537W	20		PA		7-6	33-25-21		D11508	7			SM00547		S		YC051-YL999, YR301-YR328
0537W	20		PA		7-5	33-25-21		D11508	7			SM00547		S		YN231-YN501
0538O	18		PA		7-6	33-23-11		D11508	8			SM00548		S		YC051-YL999, YR301-YR328
0538O	18		PA		7-5	33-23-11		D11508	8			SM00548		S		YN231-YN501
0539A	16		CQ		7-6	35-21-21		D11508	11			SM00549		S		YC051-YL999, YR301-YR328
0539A	16		CQ		7-4	35-21-21		D11508	11			SM00549		S		YN231-YN501
0540K	18		PA		7-6	33-27-21		D11508	10			SM00550		S		YC051-YL999, YR301-YR328
0540K	18		PA		7-4	33-27-21		D11508	10			SM00550		S		YN231-YN501
0541WY	18		PA		8-9	33-25-21		D11510	1			SM00541		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3150

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W3150	286A3150			P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
0541WY	18		PA		7-5	33-25-21	D11510				SM00541		S		YN231-YN501
0542WV	22		PA		8-9	33-27-21	D11510				SM00542		S		YC051-YL999, YR301-YR328
0542WV	22		PA		7-3	33-27-21	D11510				SM00542		S		YN231-YN501
0543WG	22		PA		8-9	33-27-21	D11510				SM00543		S		YC051-YL999, YR301-YR328
0543WG	22		PA		7-3	33-27-21	D11510				SM00543		S		YN231-YN501
0544WO	22		PA		8-9	33-27-21	D11510				SM00544		S		YC051-YL999, YR301-YR328
0544WO	22		PA		7-3	33-27-21	D11510				SM00544		S		YN231-YN501
0545V	22		PA		8-9	33-27-21	D11510				SM00545		S		YC051-YL999, YR301-YR328
0545V	22		PA		7-3	33-27-21	D11510				SM00545		S		YN231-YN501
0546N	18		PA		8-9	33-23-11	D11510				SM00546		S		YC051-YL999, YR301-YR328
0546N	18		PA		7-5	33-23-11	D11510				SM00546		S		YN231-YN501
0547W	20		PA		8-9	33-25-21	D11510				SM00547		S		YC051-YL999, YR301-YR328
0547W	20		PA		7-5	33-25-21	D11510				SM00547		S		YN231-YN501
0548O	18		PA		8-9	33-23-11	D11510				SM00548		S		YC051-YL999, YR301-YR328
0548O	18		PA		7-5	33-23-11	D11510				SM00548		S		YN231-YN501
0549A	16		CQ		8-9	35-21-21	D11510				SM00549		S		YC051-YL999, YR301-YR328
0549A	16		CQ		7-3	35-21-21	D11510				SM00549		S		YN231-YN501
0550K	18		PA		8-9	33-27-21	D11510				SM00550		S		YC051-YL999, YR301-YR328
0550K	18		PA		7-3	33-27-21	D11510				SM00550		S		YN231-YN501
0551WY	18		PA		8-3	33-25-21	D11512				SM00561		S		YC051-YL999, YR301-YR328
0551WY	18		PA		8-0	33-25-21	D11512				SM00561		S		YN231-YN501
0552WV	22		PA		8-3	33-27-21	D11512				SM00562		S		YC051-YL999, YR301-YR328
0552WV	22		PA		8-5	33-27-21	D11512				SM00562		S		YN231-YN501
0553WG	22		PA		8-3	33-27-21	D11512				SM00563		S		YC051-YL999, YR301-YR328
0553WG	22		PA		8-5	33-27-21	D11512				SM00563		S		YN231-YN501
0554WO	22		PA		8-3	33-27-21	D11512				SM00564		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3150

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
0554WO	22		PA		8-5		33-27-21	D11512				SM00564		S		YN231-YN501
0555V	22		PA		8-3		33-27-21	D11512				SM00565		S		YC051-YL999, YR301-YR328
0555V	22		PA		8-5		33-27-21	D11512				SM00565		S		YN231-YN501
0556N	18		PA		8-3		33-23-11	D11512				SM00566		S		YC051-YL999, YR301-YR328
0556N	18		PA		8-0		33-23-11	D11512				SM00566		S		YN231-YN501
0557W	20		PA		8-3		33-25-21	D11512				SM00567		S		YC051-YL999, YR301-YR328
0557W	20		PA		8-0		33-25-21	D11512				SM00567		S		YN231-YN501
0558O	18		PA		8-3		33-23-11	D11512				SM00568		S		YC051-YL999, YR301-YR328
0558O	18		PA		8-0		33-23-11	D11512				SM00568		S		YN231-YN501
0559A	16		CQ		8-3		35-21-21	D11512				SM00569		S		YC051-YL999, YR301-YR328
0559A	16		CQ		8-5		35-21-21	D11512				SM00569		S		YN231-YN501
0560K	18		PA		8-3		33-27-21	D11512				SM00570		S		YC051-YL999, YR301-YR328
0560K	18		PA		8-5		33-27-21	D11512				SM00570		S		YN231-YN501
0561WY	18		PA		9-9		33-25-21	D11514				SM00561		S		YC051-YL999, YR301-YR328
0561WY	18		PA		8-9		33-25-21	D11514				SM00561		S		YN231-YN501
0562WV	22		PA		9-9		33-27-21	D11514				SM00562		S		YC051-YL999, YR301-YR328
0562WV	22		PA		8-10		33-27-21	D11514				SM00562		S		YN231-YN501
0563WG	22		PA		9-9		33-27-21	D11514				SM00563		S		YC051-YL999, YR301-YR328
0563WG	22		PA		8-10		33-27-21	D11514				SM00563		S		YN231-YN501
0564WO	22		PA		9-9		33-27-21	D11514				SM00564		S		YC051-YL999, YR301-YR328
0564WO	22		PA		8-10		33-27-21	D11514				SM00564		S		YN231-YN501
0565V	22		PA		9-9		33-27-21	D11514				SM00565		S		YC051-YL999, YR301-YR328
0565V	22		PA		8-10		33-27-21	D11514				SM00565		S		YN231-YN501
0566N	18		PA		9-9		33-23-11	D11514				SM00566		S		YC051-YL999, YR301-YR328
0566N	18		PA		8-9		33-23-11	D11514				SM00566		S		YN231-YN501
0567W	20		PA		9-9		33-25-21	D11514				SM00567		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3150

Page 18

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
0567W	20		PA		8-9	33-25-21	D11514		7		SM00567		S		YN231-YN501
0568O	18		PA		9-9	33-23-11	D11514		8		SM00568		S		YC051-YL999, YR301-YR328
0568O	18		PA		8-9	33-23-11	D11514		8		SM00568		S		YN231-YN501
0569A	16		CQ		9-9	35-21-21	D11514		11		SM00569		S		YC051-YL999, YR301-YR328
0569A	16		CQ		8-10	35-21-21	D11514		11		SM00569		S		YN231-YN501
0570K	18		PA		9-9	33-27-21	D11514		10		SM00570		S		YC051-YL999, YR301-YR328
0570K	18		PA		8-10	33-27-21	D11514		10		SM00570		S		YN231-YN501
0571WY	18		PA		8-10	33-25-21	D11516		1		SM00581		S		YC051-YL999, YR301-YR328
0571WY	18		PA		8-6	33-25-21	D11516		1		SM00581		S		YN231-YN501
0572WV	22		PA		8-10	33-27-21	D11516		2		SM00582		S		YC051-YL999, YR301-YR328
0572WV	22		PA		9-0	33-27-21	D11516		2		SM00582		S		YN231-YN501
0573WG	22		PA		8-10	33-27-21	D11516		3		SM00583		S		YC051-YL999, YR301-YR328
0573WG	22		PA		9-0	33-27-21	D11516		3		SM00583		S		YN231-YN501
0574WO	22		PA		8-10	33-27-21	D11516		4		SM00584		S		YC051-YL999, YR301-YR328
0574WO	22		PA		9-0	33-27-21	D11516		4		SM00584		S		YN231-YN501
0575V	22		PA		8-10	33-27-21	D11516		5		SM00585		S		YC051-YL999, YR301-YR328
0575V	22		PA		9-0	33-27-21	D11516		5		SM00585		S		YN231-YN501
0576N	18		PA		8-10	33-23-11	D11516		6		SM00586		S		YC051-YL999, YR301-YR328
0576N	18		PA		8-6	33-23-11	D11516		6		SM00586		S		YN231-YN501
0577W	20		PA		8-10	33-25-21	D11516		7		SM00587		S		YC051-YL999, YR301-YR328
0577W	20		PA		8-6	33-25-21	D11516		7		SM00587		S		YN231-YN501
0578O	18		PA		8-10	33-23-11	D11516		8		SM00588		S		YC051-YL999, YR301-YR328
0578O	18		PA		8-6	33-23-11	D11516		8		SM00588		S		YN231-YN501
0579A	16		CQ		8-10	35-21-21	D11516		11		SM00589		S		YC051-YL999, YR301-YR328
0579A	16		CQ		9-0	35-21-21	D11516		11		SM00589		S		YN231-YN501
0580K	18		PA		8-10	33-27-21	D11516		10		SM00590		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3150

Page 19

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
0580K	18		PA		9-0	33-27-21		D11516	10			SM00590		S		YN231-YN501
0581WY	18		PA		8-5	33-25-21		D11518	1			SM00581		S		YC051-YL999, YR301-YR328
0581WY	18		PA		11-5	33-25-21		D11518	1			SM00581		S		YN231-YN501
0582WV	22		PA		8-5	33-27-21		D11518	2			SM00582		S		YC051-YL999, YR301-YR328
0582WV	22		PA		11-10	33-27-21		D11518	2			SM00582		S		YN231-YN501
0583WG	22		PA		8-5	33-27-21		D11518	3			SM00583		S		YC051-YL999, YR301-YR328
0583WG	22		PA		11-10	33-27-21		D11518	3			SM00583		S		YN231-YN501
0584WO	22		PA		8-5	33-27-21		D11518	4			SM00584		S		YC051-YL999, YR301-YR328
0584WO	22		PA		11-10	33-27-21		D11518	4			SM00584		S		YN231-YN501
0585V	22		PA		8-5	33-27-21		D11518	5			SM00585		S		YC051-YL999, YR301-YR328
0585V	22		PA		11-10	33-27-21		D11518	5			SM00585		S		YN231-YN501
0586N	18		PA		8-5	33-23-11		D11518	6			SM00586		S		YC051-YL999, YR301-YR328
0586N	18		PA		11-5	33-23-11		D11518	6			SM00586		S		YN231-YN501
0587W	20		PA		8-5	33-25-21		D11518	7			SM00587		S		YC051-YL999, YR301-YR328
0587W	20		PA		11-5	33-25-21		D11518	7			SM00587		S		YN231-YN501
0588O	18		PA		8-5	33-23-11		D11518	8			SM00588		S		YC051-YL999, YR301-YR328
0588O	18		PA		11-5	33-23-11		D11518	8			SM00588		S		YN231-YN501
0589A	16		CQ		8-5	35-21-21		D11518	11			SM00589		S		YC051-YL999, YR301-YR328
0589A	16		CQ		11-10	35-21-21		D11518	11			SM00589		S		YN231-YN501
0590K	18		PA		8-5	33-27-21		D11518	10			SM00590		S		YC051-YL999, YR301-YR328
0590K	18		PA		11-10	33-27-21		D11518	10			SM00590		S		YN231-YN501
0591WY	18		PA		8-11	33-25-21		D11520	1			SM00601		S		YC051-YL999, YR301-YR328
0591WY	18		PA		8-1	33-25-21		D11520	1			SM00641		S		YN231-YN501
0592WV	22		PA		8-11	33-27-21		D11520	2			SM00602		S		YC051-YL999, YR301-YR328
0592WV	22		PA		8-0	33-27-21		D11520	2			SM00642		S		YN231-YN501
0593WG	22		PA		8-11	33-27-21		D11520	3			SM00603		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3150

Page 20

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
0593WG	22		PA		8-0	33-27-21	D11520				SM00643		S		YN231-YN501
0594WO	22		PA		8-11	33-27-21	D11520				SM00604		S		YC051-YL999, YR301-YR328
0594WO	22		PA		8-0	33-27-21	D11520				SM00644		S		YN231-YN501
0595V	22		PA		8-11	33-27-21	D11520				SM00605		S		YC051-YL999, YR301-YR328
0595V	22		PA		8-0	33-27-21	D11520				SM00645		S		YN231-YN501
0596N	18		PA		8-11	33-23-11	D11520				SM00606		S		YC051-YL999, YR301-YR328
0596N	18		PA		8-1	33-23-11	D11520				SM00646		S		YN231-YN501
0597W	20		PA		8-11	33-25-21	D11520				SM00607		S		YC051-YL999, YR301-YR328
0597W	20		PA		8-1	33-25-21	D11520				SM00647		S		YN231-YN501
0598O	18		PA		8-11	33-23-11	D11520				SM00608		S		YC051-YL999, YR301-YR328
0598O	18		PA		8-1	33-23-11	D11520				SM00648		S		YN231-YN501
0599A	16		CQ		8-11	35-21-21	D11520				SM00609		S		YC051-YL999, YR301-YR328
0599A	16		CQ		8-0	35-21-21	D11520				SM00649		S		YN231-YN501
0600K	18		PA		8-11	33-27-21	D11520				SM00610		S		YC051-YL999, YR301-YR328
0600K	18		PA		8-0	33-27-21	D11520				SM00650		S		YN231-YN501
0601WY	18		PA		8-3	33-25-21	D11522				SM00601		S		YC051-YL999, YR301-YR328
0602WV	22		PA		8-3	33-27-21	D11522				SM00602		S		YC051-YL999, YR301-YR328
0603WG	22		PA		8-3	33-27-21	D11522				SM00603		S		YC051-YL999, YR301-YR328
0604WO	22		PA		8-3	33-27-21	D11522				SM00604		S		YC051-YL999, YR301-YR328
0605V	22		PA		8-3	33-27-21	D11522				SM00605		S		YC051-YL999, YR301-YR328
0606N	18		PA		8-3	33-23-11	D11522				SM00606		S		YC051-YL999, YR301-YR328
0607W	20		PA		8-3	33-25-21	D11522				SM00607		S		YC051-YL999, YR301-YR328
0608O	18		PA		8-3	33-23-11	D11522				SM00608		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3150

Page 21

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)												
0609A	16		CQ		8-3	35-21-21	D11522		11			SM00609		S		YC051-YL999, YR301-YR328	
0610K	18		PA		8-3	33-27-21	D11522		10			SM00610		S		YC051-YL999, YR301-YR328	
0611WY	18		PA		8-10	33-25-21	D11524		1			SM00621		S		YC051-YL999, YR301-YR328	
0612WV	22		PA		8-10	33-27-21	D11524		2			SM00622		S		YC051-YL999, YR301-YR328	
0613WG	22		PA		8-10	33-27-21	D11524		3			SM00623		S		YC051-YL999, YR301-YR328	
0614WO	22		PA		8-10	33-27-21	D11524		4			SM00624		S		YC051-YL999, YR301-YR328	
0615V	22		PA		8-10	33-27-21	D11524		5			SM00625		S		YC051-YL999, YR301-YR328	
0616N	18		PA		8-10	33-23-11	D11524		6			SM00626		S		YC051-YL999, YR301-YR328	
0617W	20		PA		8-10	33-25-21	D11524		7			SM00627		S		YC051-YL999, YR301-YR328	
0618O	18		PA		8-10	33-23-11	D11524		8			SM00628		S		YC051-YL999, YR301-YR328	
0619A	16		CQ		8-10	35-21-21	D11524		11			SM00629		S		YC051-YL999, YR301-YR328	
0620K	18		PA		8-10	33-27-21	D11524		10			SM00630		S		YC051-YL999, YR301-YR328	
0621WY	18		PA		7-9	33-25-21	D11526		1			SM00621		S		YC051-YL999, YR301-YR328	
0622WV	22		PA		7-9	33-27-21	D11526		2			SM00622		S		YC051-YL999, YR301-YR328	
0623WG	22		PA		7-9	33-27-21	D11526		3			SM00623		S		YC051-YL999, YR301-YR328	
0624WO	22		PA		7-9	33-27-21	D11526		4			SM00624		S		YC051-YL999, YR301-YR328	
0625V	22		PA		7-9	33-27-21	D11526		5			SM00625		S		YC051-YL999, YR301-YR328	
0626N	18		PA		7-9	33-23-11	D11526		6			SM00626		S		YC051-YL999, YR301-YR328	
0627W	20		PA		7-9	33-25-21	D11526		7			SM00627		S		YC051-YL999, YR301-YR328	

WIRE LIST

D280A108

91-21-11

Section W3150

Page 22

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
0628O	18		PA		7-9	33-23-11	D11526		8		SM00628		S		YC051-YL999, YR301-YR328
0629A	16		CQ		7-9	35-21-21	D11526		11		SM00629		S		YC051-YL999, YR301-YR328
0630K	18		PA		7-9	33-27-21	D11526		10		SM00630		S		YC051-YL999, YR301-YR328
0631WY	18		PA		10-7	33-25-21	D11528		1		SM00641		S		YC051-YL999, YR301-YR328
0632WV	22		PA		10-7	33-27-21	D11528		2		SM00642		S		YC051-YL999, YR301-YR328
0633WG	22		PA		10-7	33-27-21	D11528		3		SM00643		S		YC051-YL999, YR301-YR328
0634WO	22		PA		10-7	33-27-21	D11528		4		SM00644		S		YC051-YL999, YR301-YR328
0635V	22		PA		10-7	33-27-21	D11528		5		SM00645		S		YC051-YL999, YR301-YR328
0636N	18		PA		10-7	33-23-11	D11528		6		SM00646		S		YC051-YL999, YR301-YR328
0637W	20		PA		10-7	33-25-21	D11528		7		SM00647		S		YC051-YL999, YR301-YR328
0638O	18		PA		10-7	33-23-11	D11528		8		SM00648		S		YC051-YL999, YR301-YR328
0639A	16		CQ		10-7	35-21-21	D11528		11		SM00649		S		YC051-YL999, YR301-YR328
0640K	18		PA		10-7	33-27-21	D11528		10		SM00650		S		YC051-YL999, YR301-YR328
0641WY	18		PA		10-1	33-25-21	D11530		1		SM00641		S		YC051-YL999, YR301-YR328
0641WY	18		PA		10-10	33-25-21	D11530		1		SM00641		S		YN231-YN501
0642WV	22		PA		10-1	33-27-21	D11530		2		SM00642		S		YC051-YL999, YR301-YR328
0642WV	22		PA		10-7	33-27-21	D11530		2		SM00642		S		YN231-YN501
0643WG	22		PA		10-1	33-27-21	D11530		3		SM00643		S		YC051-YL999, YR301-YR328
0643WG	22		PA		10-7	33-27-21	D11530		3		SM00643		S		YN231-YN501
0644WO	22		PA		10-1	33-27-21	D11530		4		SM00644		S		YC051-YL999, YR301-YR328
0644WO	22		PA		10-7	33-27-21	D11530		4		SM00644		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 23

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
0645V	22		PA		10-1	33-27-21	D11530		5		SM00645		S		YC051-YL999, YR301-YR328
0645V	22		PA		10-7	33-27-21	D11530		5		SM00645		S		YN231-YN501
0646N	18		PA		10-1	33-23-11	D11530		6		SM00646		S		YC051-YL999, YR301-YR328
0646N	18		PA		10-10	33-23-11	D11530		6		SM00646		S		YN231-YN501
0647W	20		PA		10-1	33-25-21	D11530		7		SM00647		S		YC051-YL999, YR301-YR328
0647W	20		PA		10-10	33-25-21	D11530		7		SM00647		S		YN231-YN501
0648O	18		PA		10-1	33-23-11	D11530		8		SM00648		S		YC051-YL999, YR301-YR328
0648O	18		PA		10-10	33-23-11	D11530		8		SM00648		S		YN231-YN501
0649A	16		CQ		10-1	35-21-21	D11530		11		SM00649		S		YC051-YL999, YR301-YR328
0649A	16		CQ		10-7	35-21-21	D11530		11		SM00649		S		YN231-YN501
0650K	18		PA		10-1	33-27-21	D11530		10		SM00650		S		YC051-YL999, YR301-YR328
0650K	18		PA		10-7	33-27-21	D11530		10		SM00650		S		YN231-YN501
0651WY	18		PA		8-0	33-25-21	D11532		1		SM00661		S		YC051-YL999, YR301-YR328
0651WY	18		PA		10-5	33-25-21	D11532		1		SM00641		S		YN231-YN501
0652WV	22		PA		8-0	33-27-21	D11532		2		SM00662		S		YC051-YL999, YR301-YR328
0652WV	22		PA		10-0	33-27-21	D11532		2		SM00642		S		YN231-YN501
0653WG	22		PA		8-0	33-27-21	D11532		3		SM00663		S		YC051-YL999, YR301-YR328
0653WG	22		PA		10-0	33-27-21	D11532		3		SM00643		S		YN231-YN501
0654WO	22		PA		8-0	33-27-21	D11532		4		SM00664		S		YC051-YL999, YR301-YR328
0654WO	22		PA		10-0	33-27-21	D11532		4		SM00644		S		YN231-YN501
0655V	22		PA		8-0	33-27-21	D11532		5		SM00665		S		YC051-YL999, YR301-YR328
0655V	22		PA		10-0	33-27-21	D11532		5		SM00645		S		YN231-YN501
0656N	18		PA		8-0	33-23-11	D11532		6		SM00666		S		YC051-YL999, YR301-YR328
0656N	18		PA		10-5	33-23-11	D11532		6		SM00646		S		YN231-YN501
0657W	20		PA		8-0	33-25-21	D11532		7		SM00667		S		YC051-YL999, YR301-YR328
0657W	20		PA		10-5	33-25-21	D11532		7		SM00647		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 24

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
0658O	18		PA		8-0	33-23-11	D11532		8		SM00668		S		YC051-YL999, YR301-YR328
0658O	18		PA		10-5	33-23-11	D11532		8		SM00648		S		YN231-YN501
0659A	16		CQ		8-0	35-21-21	D11532		11		SM00669		S		YC051-YL999, YR301-YR328
0659A	16		CQ		10-0	35-21-21	D11532		11		SM00649		S		YN231-YN501
0660K	18		PA		8-0	33-27-21	D11532		10		SM00670		S		YC051-YL999, YR301-YR328
0660K	18		PA		10-0	33-27-21	D11532		10		SM00650		S		YN231-YN501
0661WY	18		PA		8-4	33-25-21	D11534		1		SM00661		S		YC051-YL999, YR301-YR328
0661WY	18		PA		7-7	33-25-21	D11534		1		SM00661		S		YN231-YN501
0662WV	22		PA		8-4	33-27-21	D11534		2		SM00662		S		YC051-YL999, YR301-YR328
0662WV	22		PA		7-3	33-27-21	D11534		2		SM00662		S		YN231-YN501
0663WG	22		PA		8-4	33-27-21	D11534		3		SM00663		S		YC051-YL999, YR301-YR328
0663WG	22		PA		7-3	33-27-21	D11534		3		SM00663		S		YN231-YN501
0664WO	22		PA		8-4	33-27-21	D11534		4		SM00664		S		YC051-YL999, YR301-YR328
0664WO	22		PA		7-3	33-27-21	D11534		4		SM00664		S		YN231-YN501
0665V	22		PA		8-4	33-27-21	D11534		5		SM00665		S		YC051-YL999, YR301-YR328
0665V	22		PA		7-3	33-27-21	D11534		5		SM00665		S		YN231-YN501
0666N	18		PA		8-4	33-23-11	D11534		6		SM00666		S		YC051-YL999, YR301-YR328
0666N	18		PA		7-7	33-23-11	D11534		6		SM00666		S		YN231-YN501
0667W	20		PA		8-4	33-25-21	D11534		7		SM00667		S		YC051-YL999, YR301-YR328
0667W	20		PA		7-7	33-25-21	D11534		7		SM00667		S		YN231-YN501
0668O	18		PA		8-4	33-23-11	D11534		8		SM00668		S		YC051-YL999, YR301-YR328
0668O	18		PA		7-7	33-23-11	D11534		8		SM00668		S		YN231-YN501
0669A	16		CQ		8-4	35-21-21	D11534		11		SM00669		S		YC051-YL999, YR301-YR328
0669A	16		CQ		7-3	35-21-21	D11534		11		SM00669		S		YN231-YN501
0670K	18		PA		8-4	33-27-21	D11534		10		SM00670		S		YC051-YL999, YR301-YR328
0670K	18		PA		7-3	33-27-21	D11534		10		SM00670		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 25

Nov 12/2012

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150			P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
0671WY	18		PA		9-0	33-25-21	D11536				SM00681		S		YC051-YL999, YR301-YR328
0671WY	18		PA		7-5	33-25-21	D11536				SM00661		S		YN231-YN501
0672WV	22		PA		9-0	33-27-21	D11536				SM00682		S		YC051-YL999, YR301-YR328
0672WV	22		PA		7-4	33-27-21	D11536				SM00662		S		YN231-YN501
0673WG	22		PA		9-0	33-27-21	D11536				SM00683		S		YC051-YL999, YR301-YR328
0673WG	22		PA		7-4	33-27-21	D11536				SM00663		S		YN231-YN501
0674WO	22		PA		9-0	33-27-21	D11536				SM00684		S		YC051-YL999, YR301-YR328
0674WO	22		PA		7-4	33-27-21	D11536				SM00664		S		YN231-YN501
0675V	22		PA		9-0	33-27-21	D11536				SM00685		S		YC051-YL999, YR301-YR328
0675V	22		PA		7-4	33-27-21	D11536				SM00665		S		YN231-YN501
0676N	18		PA		9-0	33-23-11	D11536				SM00686		S		YC051-YL999, YR301-YR328
0676N	18		PA		7-5	33-23-11	D11536				SM00666		S		YN231-YN501
0677W	20		PA		9-0	33-25-21	D11536				SM00687		S		YC051-YL999, YR301-YR328
0677W	20		PA		7-5	33-25-21	D11536				SM00667		S		YN231-YN501
0678O	18		PA		9-0	33-23-11	D11536				SM00688		S		YC051-YL999, YR301-YR328
0678O	18		PA		7-5	33-23-11	D11536				SM00668		S		YN231-YN501
0679A	16		CQ		9-0	35-21-21	D11536				SM00689		S		YC051-YL999, YR301-YR328
0679A	16		CQ		7-4	35-21-21	D11536				SM00669		S		YN231-YN501
0680K	18		PA		9-0	33-27-21	D11536				SM00690		S		YC051-YL999, YR301-YR328
0680K	18		PA		7-4	33-27-21	D11536				SM00670		S		YN231-YN501
0681WY	18		PA		9-3	33-25-21	D11538				SM00681		S		YC051-YL999, YR301-YR328
0681WY	18		PA		8-0	33-25-21	D11538				SM00681		S		YN231-YN501
0682WV	22		PA		9-3	33-27-21	D11538				SM00682		S		YC051-YL999, YR301-YR328
0682WV	22		PA		8-1	33-27-22	D11538				SM00682		S		YN231-YN501
0683WG	22		PA		9-3	33-27-21	D11538				SM00683		S		YC051-YL999, YR301-YR328
0683WG	22		PA		8-1	33-27-22	D11538				SM00683		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 26

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150			P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
0684WO	22		PA		9-3	33-27-21	D11538		4		SM00684		S		YC051-YL999, YR301-YR328
0684WO	22		PA		8-1	33-27-22	D11538		4		SM00684		S		YN231-YN501
0685V	22		PA		9-3	33-27-21	D11538		5		SM00685		S		YC051-YL999, YR301-YR328
0685V	22		PA		8-1	33-27-22	D11538		5		SM00685		S		YN231-YN501
0686N	18		PA		9-3	33-23-11	D11538		6		SM00686		S		YC051-YL999, YR301-YR328
0686N	18		PA		8-0	33-23-11	D11538		6		SM00686		S		YN231-YN501
0687W	20		PA		9-3	33-25-21	D11538		7		SM00687		S		YC051-YL999, YR301-YR328
0687W	20		PA		8-0	33-25-21	D11538		7		SM00687		S		YN231-YN501
0688O	18		PA		9-3	33-23-11	D11538		8		SM00688		S		YC051-YL999, YR301-YR328
0688O	18		PA		8-0	33-23-11	D11538		8		SM00688		S		YN231-YN501
0689A	16		CQ		9-3	35-21-21	D11538		11		SM00689		S		YC051-YL999, YR301-YR328
0689A	16		CQ		8-1	35-21-21	D11538		11		SM00689		S		YN231-YN501
0690K	18		PA		9-3	33-27-21	D11538		10		SM00690		S		YC051-YL999, YR301-YR328
0690K	18		PA		8-1	33-27-22	D11538		10		SM00690		S		YN231-YN501
0691WY	18		PA		9-3	33-25-21	D11540		1		SM00701		S		YC051-YL999, YR301-YR328
0691WY	18		PA		9-5	33-25-21	D11540		1		SM00681		S		YN231-YN501
0692WV	22		PA		9-3	33-27-21	D11540		2		SM00702		S		YC051-YL999, YR301-YR328
0692WV	22		PA		9-2	33-27-22	D11540		2		SM00682		S		YN231-YN501
0693WG	22		PA		9-3	33-27-21	D11540		3		SM00703		S		YC051-YL999, YR301-YR328
0693WG	22		PA		9-2	33-27-22	D11540		3		SM00683		S		YN231-YN501
0694WO	22		PA		9-3	33-27-21	D11540		4		SM00704		S		YC051-YL999, YR301-YR328
0694WO	22		PA		9-2	33-27-22	D11540		4		SM00684		S		YN231-YN501
0695V	22		PA		9-3	33-27-21	D11540		5		SM00705		S		YC051-YL999, YR301-YR328
0695V	22		PA		9-2	33-27-22	D11540		5		SM00685		S		YN231-YN501
0696N	18		PA		9-3	33-23-11	D11540		6		SM00706		S		YC051-YL999, YR301-YR328
0696N	18		PA		9-5	33-23-11	D11540		6		SM00686		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 27

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
0697W	20		PA		9-3	33-25-21	D11540		7			SM00707		S		YC051-YL999, YR301-YR328
0697W	20		PA		9-5	33-25-21	D11540		7			SM00687		S		YN231-YN501
0698O	18		PA		9-3	33-23-11	D11540		8			SM00708		S		YC051-YL999, YR301-YR328
0698O	18		PA		9-5	33-23-11	D11540		8			SM00688		S		YN231-YN501
0699A	16		CQ		9-3	35-21-21	D11540		11			SM00709		S		YC051-YL999, YR301-YR328
0699A	16		CQ		9-2	35-21-21	D11540		11			SM00689		S		YN231-YN501
0700K	18		PA		9-3	33-27-21	D11540		10			SM00710		S		YC051-YL999, YR301-YR328
0700K	18		PA		9-2	33-27-22	D11540		10			SM00690		S		YN231-YN501
0701WY	18		PA		7-10	33-25-21	D11542		1			SM00701		S		YC051-YL999, YR301-YR328
0701WY	18		PA		9-10	33-25-22	D11542		1			SM00701		S		YN231-YN501
0702WV	22		PA		7-10	33-27-21	D11542		2			SM00702		S		YC051-YL999, YR301-YR328
0702WV	22		PA		9-5	33-27-22	D11542		2			SM00702		S		YN231-YN501
0703WG	22		PA		7-10	33-27-21	D11542		3			SM00703		S		YC051-YL999, YR301-YR328
0703WG	22		PA		9-5	33-27-22	D11542		3			SM00703		S		YN231-YN501
0704WO	22		PA		7-10	33-27-21	D11542		4			SM00704		S		YC051-YL999, YR301-YR328
0704WO	22		PA		9-5	33-27-22	D11542		4			SM00704		S		YN231-YN501
0705V	22		PA		7-10	33-27-21	D11542		5			SM00705		S		YC051-YL999, YR301-YR328
0705V	22		PA		9-5	33-27-22	D11542		5			SM00705		S		YN231-YN501
0706N	18		PA		7-10	33-23-11	D11542		6			SM00706		S		YC051-YL999, YR301-YR328
0706N	18		PA		9-10	33-23-12	D11542		6			SM00706		S		YN231-YN501
0707W	20		PA		7-10	33-25-21	D11542		7			SM00707		S		YC051-YL999, YR301-YR328
0707W	20		PA		9-10	33-25-22	D11542		7			SM00707		S		YN231-YN501
0708O	18		PA		7-10	33-23-11	D11542		8			SM00708		S		YC051-YL999, YR301-YR328
0708O	18		PA		9-10	33-23-12	D11542		8			SM00708		S		YN231-YN501
0709A	16		CQ		7-10	35-21-21	D11542		11			SM00709		S		YC051-YL999, YR301-YR328
0709A	16		CQ		9-5	35-21-21	D11542		11			SM00709		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 28

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
0710K	18		PA		7-10	33-27-21	D11542		10		SM00710		S		YC051-YL999, YR301-YR328
0710K	18		PA		9-5	33-27-22	D11542		10		SM00710		S		YN231-YN501
0711WY	18		PA		8-5	33-25-21	D11544		1		SM00721		S		YC051-YL999, YR301-YR328
0711WY	18		PA		12-3	33-25-22	D11544		1		SM00701		S		YN231-YN501
0712WV	22		PA		8-5	33-27-21	D11544		2		SM00722		S		YC051-YL999, YR301-YR328
0712WV	22		PA		12-0	33-27-22	D11544		2		SM00702		S		YN231-YN501
0713WG	22		PA		8-5	33-27-21	D11544		3		SM00723		S		YC051-YL999, YR301-YR328
0713WG	22		PA		12-0	33-27-22	D11544		3		SM00703		S		YN231-YN501
0714WO	22		PA		8-5	33-27-21	D11544		4		SM00724		S		YC051-YL999, YR301-YR328
0714WO	22		PA		12-0	33-27-22	D11544		4		SM00704		S		YN231-YN501
0715V	22		PA		8-5	33-27-21	D11544		5		SM00725		S		YC051-YL999, YR301-YR328
0715V	22		PA		12-0	33-27-22	D11544		5		SM00705		S		YN231-YN501
0716N	18		PA		8-5	33-23-11	D11544		6		SM00726		S		YC051-YL999, YR301-YR328
0716N	18		PA		12-3	33-23-12	D11544		6		SM00706		S		YN231-YN501
0717W	20		PA		8-5	33-25-21	D11544		7		SM00727		S		YC051-YL999, YR301-YR328
0717W	20		PA		12-3	33-25-22	D11544		7		SM00707		S		YN231-YN501
0718O	18		PA		8-5	33-23-11	D11544		8		SM00728		S		YC051-YL999, YR301-YR328
0718O	18		PA		12-3	33-23-12	D11544		8		SM00708		S		YN231-YN501
0719A	16		CQ		8-5	35-21-21	D11544		11		SM00729		S		YC051-YL999, YR301-YR328
0719A	16		CQ		12-0	35-21-21	D11544		11		SM00709		S		YN231-YN501
0720K	18		PA		8-5	33-27-21	D11544		10		SM00730		S		YC051-YL999, YR301-YR328
0720K	18		PA		12-0	33-27-22	D11544		10		SM00710		S		YN231-YN501
0721WY	18		PA		10-4	33-25-21	D11546		1		SM00721		S		YC051-YL999, YR301-YR328
0721WY	18		PA		9-11	33-25-22	D11546		1		SM00721		S		YN231-YN501
0722WV	22		PA		10-4	33-27-21	D11546		2		SM00722		S		YC051-YL999, YR301-YR328
0722WV	22		PA		9-11	33-27-22	D11546		2		SM00722		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 29

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
0723WG	22		PA		10-4	33-27-21	D11546		3		SM00723		S		YC051-YL999, YR301-YR328
0723WG	22		PA		9-11	33-27-22	D11546		3		SM00723		S		YN231-YN501
0724WO	22		PA		10-4	33-27-21	D11546		4		SM00724		S		YC051-YL999, YR301-YR328
0724WO	22		PA		9-11	33-27-22	D11546		4		SM00724		S		YN231-YN501
0725V	22		PA		10-4	33-27-21	D11546		5		SM00725		S		YC051-YL999, YR301-YR328
0725V	22		PA		9-11	33-27-22	D11546		5		SM00725		S		YN231-YN501
0726N	18		PA		10-4	33-23-11	D11546		6		SM00726		S		YC051-YL999, YR301-YR328
0726N	18		PA		9-11	33-23-12	D11546		6		SM00726		S		YN231-YN501
0727W	20		PA		10-4	33-25-21	D11546		7		SM00727		S		YC051-YL999, YR301-YR328
0727W	20		PA		9-11	33-25-22	D11546		7		SM00727		S		YN231-YN501
0728O	18		PA		10-4	33-23-11	D11546		8		SM00728		S		YC051-YL999, YR301-YR328
0728O	18		PA		9-11	33-23-12	D11546		8		SM00728		S		YN231-YN501
0729A	16		CQ		10-4	35-21-21	D11546		11		SM00729		S		YC051-YL999, YR301-YR328
0729A	16		CQ		9-11	35-21-21	D11546		11		SM00729		S		YN231-YN501
0730K	18		PA		10-4	33-27-21	D11546		10		SM00730		S		YC051-YL999, YR301-YR328
0730K	18		PA		9-11	33-27-22	D11546		10		SM00730		S		YN231-YN501
0731WY	18		PA		8-8	33-25-22	D11548		1		SM00741		S		YC051-YL999, YR301-YR328
0731WY	18		PA		9-5	33-25-22	D11548		1		SM00721		S		YN231-YN501
0732WV	22		PA		8-8	33-27-22	D11548		2		SM00742		S		YC051-YL999, YR301-YR328
0732WV	22		PA		9-4	33-27-22	D11548		2		SM00722		S		YN231-YN501
0733WG	22		PA		8-8	33-27-22	D11548		3		SM00743		S		YC051-YL999, YR301-YR328
0733WG	22		PA		9-4	33-27-22	D11548		3		SM00723		S		YN231-YN501
0734WO	22		PA		8-8	33-27-22	D11548		4		SM00744		S		YC051-YL999, YR301-YR328
0734WO	22		PA		9-4	33-27-22	D11548		4		SM00724		S		YN231-YN501
0735V	22		PA		8-8	33-27-22	D11548		5		SM00745		S		YC051-YL999, YR301-YR328
0735V	22		PA		9-4	33-27-22	D11548		5		SM00725		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 30

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
0736N	18		PA		8-8	33-23-12	D11548		6		SM00746		S		YC051-YL999, YR301-YR328
0736N	18		PA		9-5	33-23-12	D11548		6		SM00726		S		YN231-YN501
0737W	20		PA		8-8	33-25-22	D11548		7		SM00747		S		YC051-YL999, YR301-YR328
0737W	20		PA		9-5	33-25-22	D11548		7		SM00727		S		YN231-YN501
0738O	18		PA		8-8	33-23-12	D11548		8		SM00748		S		YC051-YL999, YR301-YR328
0738O	18		PA		9-5	33-23-12	D11548		8		SM00728		S		YN231-YN501
0739A	16		CQ		8-8	35-21-21	D11548		11		SM00749		S		YC051-YL999, YR301-YR328
0739A	16		CQ		9-4	35-21-21	D11548		11		SM00729		S		YN231-YN501
0740K	18		PA		8-8	33-27-22	D11548		10		SM00750		S		YC051-YL999, YR301-YR328
0740K	18		PA		9-4	33-27-22	D11548		10		SM00730		S		YN231-YN501
0741WY	18		PA		8-8	33-25-22	D11550		1		SM00741		S		YC051-YL999, YR301-YR328
0741WY	18		PA		8-2	33-25-22	D11550		1		SM00741		S		YN231-YN501
0742WV	22		PA		8-8	33-27-22	D11550		2		SM00742		S		YC051-YL999, YR301-YR328
0742WV	22		PA		8-0	33-27-22	D11550		2		SM00742		S		YN231-YN501
0743WG	22		PA		8-8	33-27-22	D11550		3		SM00743		S		YC051-YL999, YR301-YR328
0743WG	22		PA		8-0	33-27-22	D11550		3		SM00743		S		YN231-YN501
0744WO	22		PA		8-8	33-27-22	D11550		4		SM00744		S		YC051-YL999, YR301-YR328
0744WO	22		PA		8-0	33-27-22	D11550		4		SM00744		S		YN231-YN501
0745V	22		PA		8-8	33-27-22	D11550		5		SM00745		S		YC051-YL999, YR301-YR328
0745V	22		PA		8-0	33-27-22	D11550		5		SM00745		S		YN231-YN501
0746N	18		PA		8-8	33-23-12	D11550		6		SM00746		S		YC051-YL999, YR301-YR328
0746N	18		PA		8-2	33-23-12	D11550		6		SM00746		S		YN231-YN501
0747W	20		PA		8-8	33-25-22	D11550		7		SM00747		S		YC051-YL999, YR301-YR328
0747W	20		PA		8-2	33-25-22	D11550		7		SM00747		S		YN231-YN501
0748O	18		PA		8-8	33-23-12	D11550		8		SM00748		S		YC051-YL999, YR301-YR328
0748O	18		PA		8-2	33-23-12	D11550		8		SM00748		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 31

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150			P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
0749A	16		CQ		8-8	35-21-21	D11550	11			SM00749		S		YC051-YL999, YR301-YR328
0749A	16		CQ		8-0	35-21-21	D11550	11			SM00749		S		YN231-YN501
0750K	18		PA		8-8	33-27-22	D11550	10			SM00750		S		YC051-YL999, YR301-YR328
0750K	18		PA		8-0	33-27-22	D11550	10			SM00750		S		YN231-YN501
0751WY	18		PA		8-5	33-25-22	D11552	1			SM00761		S		YC051-YL999, YR301-YR328
0751WY	18		PA		8-11	33-25-22	D11552	1			SM00741		S		YN231-YN501
0752WV	22		PA		8-5	33-27-22	D11552	2			SM00762		S		YC051-YL999, YR301-YR328
0752WV	22		PA		8-11	33-27-22	D11552	2			SM00742		S		YN231-YN501
0753WG	22		PA		8-5	33-27-22	D11552	3			SM00763		S		YC051-YL999, YR301-YR328
0753WG	22		PA		8-11	33-27-22	D11552	3			SM00743		S		YN231-YN501
0754WO	22		PA		8-5	33-27-22	D11552	4			SM00764		S		YC051-YL999, YR301-YR328
0754WO	22		PA		8-11	33-27-22	D11552	4			SM00744		S		YN231-YN501
0755V	22		PA		8-5	33-27-22	D11552	5			SM00765		S		YC051-YL999, YR301-YR328
0755V	22		PA		8-11	33-27-22	D11552	5			SM00745		S		YN231-YN501
0756N	18		PA		8-5	33-23-12	D11552	6			SM00766		S		YC051-YL999, YR301-YR328
0756N	18		PA		8-11	33-23-12	D11552	6			SM00746		S		YN231-YN501
0757W	20		PA		8-5	33-25-22	D11552	7			SM00767		S		YC051-YL999, YR301-YR328
0757W	20		PA		8-11	33-25-22	D11552	7			SM00747		S		YN231-YN501
0758O	18		PA		8-5	33-23-12	D11552	8			SM00768		S		YC051-YL999, YR301-YR328
0758O	18		PA		8-11	33-23-12	D11552	8			SM00748		S		YN231-YN501
0759A	16		CQ		8-5	35-21-21	D11552	11			SM00769		S		YC051-YL999, YR301-YR328
0759A	16		CQ		8-11	35-21-21	D11552	11			SM00749		S		YN231-YN501
0760K	18		PA		8-5	33-27-22	D11552	10			SM00770		S		YC051-YL999, YR301-YR328
0760K	18		PA		8-11	33-27-22	D11552	10			SM00750		S		YN231-YN501
0761WY	18		PA		7-8	33-25-22	D11554	1			SM00761		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3150

Page 32

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150			P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
0762WV	22		PA		7-8	33-27-22	D11554		2		SM00762		S		YC051-YL999, YR301-YR328
0763WG	22		PA		7-8	33-27-22	D11554		3		SM00763		S		YC051-YL999, YR301-YR328
0764WO	22		PA		7-8	33-27-22	D11554		4		SM00764		S		YC051-YL999, YR301-YR328
0765V	22		PA		7-8	33-27-22	D11554		5		SM00765		S		YC051-YL999, YR301-YR328
0766N	18		PA		7-8	33-23-12	D11554		6		SM00766		S		YC051-YL999, YR301-YR328
0767W	20		PA		7-8	33-25-22	D11554		7		SM00767		S		YC051-YL999, YR301-YR328
0768O	18		PA		7-8	33-23-12	D11554		8		SM00768		S		YC051-YL999, YR301-YR328
0769A	16		CQ		7-8	35-21-21	D11554		11		SM00769		S		YC051-YL999, YR301-YR328
0770K	18		PA		7-8	33-27-22	D11554		10		SM00770		S		YC051-YL999, YR301-YR328
0771WY	18		PA		7-2	33-25-22	D11556		1		SM00781		S		YC051-YL999, YR301-YR328
0772WV	22		PA		7-2	33-27-22	D11556		2		SM00782		S		YC051-YL999, YR301-YR328
0773WG	22		PA		7-2	33-27-22	D11556		3		SM00783		S		YC051-YL999, YR301-YR328
0774WO	22		PA		7-2	33-27-22	D11556		4		SM00784		S		YC051-YL999, YR301-YR328
0775V	22		PA		7-2	33-27-22	D11556		5		SM00785		S		YC051-YL999, YR301-YR328
0776N	18		PA		7-2	33-23-12	D11556		6		SM00786		S		YC051-YL999, YR301-YR328
0777W	20		PA		7-2	33-25-22	D11556		7		SM00787		S		YC051-YL999, YR301-YR328
0778O	18		PA		7-2	33-23-12	D11556		8		SM00788		S		YC051-YL999, YR301-YR328
0779A	16		CQ		7-2	35-21-21	D11556		11		SM00789		S		YC051-YL999, YR301-YR328
0780K	18		PA		7-2	33-27-22	D11556		10		SM00790		S		YC051-YL999, YR301-YR328

WIRE LIST
D280A108

91-21-11
Section W3150
Page 33
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150			P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
0781WY	18		PA		8-9	33-25-22	D11558		1		SM00781		S		YC051-YL999, YR301-YR328
0782WV	22		PA		8-9	33-27-22	D11558		2		SM00782		S		YC051-YL999, YR301-YR328
0783WG	22		PA		8-9	33-27-22	D11558		3		SM00783		S		YC051-YL999, YR301-YR328
0784WO	22		PA		8-9	33-27-22	D11558		4		SM00784		S		YC051-YL999, YR301-YR328
0785V	22		PA		8-9	33-27-22	D11558		5		SM00785		S		YC051-YL999, YR301-YR328
0786N	18		PA		8-9	33-23-12	D11558		6		SM00786		S		YC051-YL999, YR301-YR328
0787W	20		PA		8-9	33-25-22	D11558		7		SM00787		S		YC051-YL999, YR301-YR328
0788O	18		PA		8-9	33-23-12	D11558		8		SM00788		S		YC051-YL999, YR301-YR328
0789A	16		CQ		8-9	35-21-21	D11558		11		SM00789		S		YC051-YL999, YR301-YR328
0790K	18		PA		8-9	33-27-22	D11558		10		SM00790		S		YC051-YL999, YR301-YR328
0791WY	18		PA		7-9	33-25-22	D11560		1		SM00801		S		YC051-YL999, YR301-YR328
0792WV	22		PA		7-9	33-27-22	D11560		2		SM00802		S		YC051-YL999, YR301-YR328
0793WG	22		PA		7-9	33-27-22	D11560		3		SM00803		S		YC051-YL999, YR301-YR328
0794WO	22		PA		7-9	33-27-22	D11560		4		SM00804		S		YC051-YL999, YR301-YR328
0795V	22		PA		7-9	33-27-22	D11560		5		SM00805		S		YC051-YL999, YR301-YR328
0796N	18		PA		7-9	33-23-12	D11560		6		SM00806		S		YC051-YL999, YR301-YR328
0797W	20		PA		7-9	33-25-22	D11560		7		SM00807		S		YC051-YL999, YR301-YR328
0798O	18		PA		7-9	33-23-12	D11560		8		SM00808		S		YC051-YL999, YR301-YR328
0799A	16		CQ		7-9	35-21-21	D11560		11		SM00809		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3150

Page 34

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
0800K	18		PA		7-9	33-27-22	D11560		10		SM00810		S		YC051-YL999, YR301-YR328
0801WY	18		PA		9-4	33-25-22	D11562		1		SM00801		S		YC051-YL999, YR301-YR328
0802WV	22		PA		9-4	33-27-22	D11562		2		SM00802		S		YC051-YL999, YR301-YR328
0803WG	22		PA		9-4	33-27-22	D11562		3		SM00803		S		YC051-YL999, YR301-YR328
0804WO	22		PA		9-4	33-27-22	D11562		4		SM00804		S		YC051-YL999, YR301-YR328
0805V	22		PA		9-4	33-27-22	D11562		5		SM00805		S		YC051-YL999, YR301-YR328
0806N	18		PA		9-4	33-23-12	D11562		6		SM00806		S		YC051-YL999, YR301-YR328
0807W	20		PA		9-4	33-25-22	D11562		7		SM00807		S		YC051-YL999, YR301-YR328
0808O	18		PA		9-4	33-23-12	D11562		8		SM00808		S		YC051-YL999, YR301-YR328
0809A	16		CQ		9-4	35-21-21	D11562		11		SM00809		S		YC051-YL999, YR301-YR328
0810K	18		PA		9-4	33-27-22	D11562		10		SM00810		S		YC051-YL999, YR301-YR328
0811WY	18		PA		7-10	33-25-22	D11564		1		SM00821		S		YC051-YL999, YR301-YR328
0811WY	18		PA		9-5	33-25-22	D11564		1		SM00821		S		YN231-YN501
0812WV	22		PA		7-10	33-27-22	D11564		2		SM00822		S		YC051-YL999, YR301-YR328
0812WV	22		PA		9-3	33-27-22	D11564		2		SM00822		S		YN231-YN501
0813WG	22		PA		7-10	33-27-22	D11564		3		SM00823		S		YC051-YL999, YR301-YR328
0813WG	22		PA		9-3	33-27-22	D11564		3		SM00823		S		YN231-YN501
0814WO	22		PA		7-10	33-27-22	D11564		4		SM00824		S		YC051-YL999, YR301-YR328
0814WO	22		PA		9-3	33-27-22	D11564		4		SM00824		S		YN231-YN501
0815V	22		PA		7-10	33-27-22	D11564		5		SM00825		S		YC051-YL999, YR301-YR328
0815V	22		PA		9-3	33-27-22	D11564		5		SM00825		S		YN231-YN501
0816N	18		PA		7-10	33-23-12	D11564		6		SM00826		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3150

Page 35

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
0816N	18		PA		9-5	33-23-12		D11564	6			SM00826		S		YN231-YN501
0817W	20		PA		7-10	33-25-22		D11564	7			SM00827		S		YC051-YL999, YR301-YR328
0817W	20		PA		9-5	33-25-22		D11564	7			SM00827		S		YN231-YN501
0818O	18		PA		7-10	33-23-12		D11564	8			SM00828		S		YC051-YL999, YR301-YR328
0818O	18		PA		9-5	33-23-12		D11564	8			SM00828		S		YN231-YN501
0819A	16		CQ		7-10	35-21-21		D11564	11			SM00829		S		YC051-YL999, YR301-YR328
0819A	16		CQ		9-3	35-21-21		D11564	11			SM00829		S		YN231-YN501
0820K	18		PA		7-10	33-27-22		D11564	10			SM00830		S		YC051-YL999, YR301-YR328
0820K	18		PA		9-3	33-27-22		D11564	10			SM00830		S		YN231-YN501
0821WY	18		PA		9-4	33-25-22		D11566	1			SM00821		S		YC051-YL999, YR301-YR328
0821WY	18		PA		14-10	33-25-22		D11566	1			SM00821		S		YN231-YN501
0822WV	22		PA		9-4	33-27-22		D11566	2			SM00822		S		YC051-YL999, YR301-YR328
0822WV	22		PA		14-10	33-27-22		D11566	2			SM00822		S		YN231-YN501
0823WG	22		PA		9-4	33-27-22		D11566	3			SM00823		S		YC051-YL999, YR301-YR328
0823WG	22		PA		14-10	33-27-22		D11566	3			SM00823		S		YN231-YN501
0824WO	22		PA		9-4	33-27-22		D11566	4			SM00824		S		YC051-YL999, YR301-YR328
0824WO	22		PA		14-10	33-27-22		D11566	4			SM00824		S		YN231-YN501
0825V	22		PA		9-4	33-27-22		D11566	5			SM00825		S		YC051-YL999, YR301-YR328
0825V	22		PA		14-10	33-27-22		D11566	5			SM00825		S		YN231-YN501
0826N	18		PA		9-4	33-23-12		D11566	6			SM00826		S		YC051-YL999, YR301-YR328
0826N	18		PA		14-10	33-23-12		D11566	6			SM00826		S		YN231-YN501
0827W	20		PA		9-4	33-25-22		D11566	7			SM00827		S		YC051-YL999, YR301-YR328
0827W	20		PA		14-10	33-25-22		D11566	7			SM00827		S		YN231-YN501
0828O	18		PA		9-4	33-23-12		D11566	8			SM00828		S		YC051-YL999, YR301-YR328
0828O	18		PA		14-10	33-23-12		D11566	8			SM00828		S		YN231-YN501
0829A	16		CQ		9-4	35-21-21		D11566	11			SM00829		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3150

Page 36

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
0829A	16	CQ		14-10	35-21-21	D11566		11			SM00829		S		YN231-YN501	
0830K	18	PA		9-4	33-27-22	D11566		10			SM00830		S		YC051-YL999, YR301-YR328	
0830K	18	PA		14-10	33-27-22	D11566		10			SM00830		S		YN231-YN501	
0831WY	18	PA		8-3	33-25-22	D11568		1			SM00841		S		YC051-YL999, YR301-YR328	
0831WY	18	PA		9-0	33-25-22	D11568		1			SM00841		S		YN231-YN501	
0832WV	22	PA		8-3	33-27-22	D11568		2			SM00842		S		YC051-YL999, YR301-YR328	
0832WV	22	PA		8-11	33-27-22	D11568		2			SM00842		S		YN231-YN501	
0833WG	22	PA		8-3	33-27-22	D11568		3			SM00843		S		YC051-YL999, YR301-YR328	
0833WG	22	PA		8-11	33-27-22	D11568		3			SM00843		S		YN231-YN501	
0834WO	22	PA		8-3	33-27-22	D11568		4			SM00844		S		YC051-YL999, YR301-YR328	
0834WO	22	PA		8-11	33-27-22	D11568		4			SM00844		S		YN231-YN501	
0835V	22	PA		8-3	33-27-22	D11568		5			SM00845		S		YC051-YL999, YR301-YR328	
0835V	22	PA		8-11	33-27-22	D11568		5			SM00845		S		YN231-YN501	
0836N	18	PA		8-3	33-23-12	D11568		6			SM00846		S		YC051-YL999, YR301-YR328	
0836N	18	PA		9-0	33-23-12	D11568		6			SM00846		S		YN231-YN501	
0837W	20	PA		8-3	33-25-22	D11568		7			SM00847		S		YC051-YL999, YR301-YR328	
0837W	20	PA		9-0	33-25-22	D11568		7			SM00847		S		YN231-YN501	
0838O	18	PA		8-3	33-23-12	D11568		8			SM00848		S		YC051-YL999, YR301-YR328	
0838O	18	PA		9-0	33-23-12	D11568		8			SM00848		S		YN231-YN501	
0839A	16	CQ		8-3	35-21-21	D11568		11			SM00849		S		YC051-YL999, YR301-YR328	
0839A	16	CQ		8-11	35-21-21	D11568		11			SM00849		S		YN231-YN501	
0840K	18	PA		8-3	33-27-22	D11568		10			SM00850		S		YC051-YL999, YR301-YR328	
0840K	18	PA		8-11	33-27-22	D11568		10			SM00850		S		YN231-YN501	
0841WY	18	PA		9-1	33-25-22	D11570		1			SM00841		S		YC051-YL999, YR301-YR328	
0841WY	18	PA		9-9	33-25-22	D11570		1			SM00841		S		YN231-YN501	
0842WV	22	PA		9-1	33-27-22	D11570		2			SM00842		S		YC051-YL999, YR301-YR328	

WIRE LIST

D280A108

91-21-11

Section W3150

Page 37

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)												
0842WV	22		PA		9-11	33-27-22		D11570		2			SM00842		S		YN231-YN501
0843WG	22		PA		9-1	33-27-22		D11570		3			SM00843		S		YC051-YL999, YR301-YR328
0843WG	22		PA		9-11	33-27-22		D11570		3			SM00843		S		YN231-YN501
0844WO	22		PA		9-1	33-27-22		D11570		4			SM00844		S		YC051-YL999, YR301-YR328
0844WO	22		PA		9-11	33-27-22		D11570		4			SM00844		S		YN231-YN501
0845V	22		PA		9-1	33-27-22		D11570		5			SM00845		S		YC051-YL999, YR301-YR328
0845V	22		PA		9-11	33-27-22		D11570		5			SM00845		S		YN231-YN501
0846N	18		PA		9-1	33-23-12		D11570		6			SM00846		S		YC051-YL999, YR301-YR328
0846N	18		PA		9-9	33-23-12		D11570		6			SM00846		S		YN231-YN501
0847W	20		PA		9-1	33-25-22		D11570		7			SM00847		S		YC051-YL999, YR301-YR328
0847W	20		PA		9-9	33-25-22		D11570		7			SM00847		S		YN231-YN501
0848O	18		PA		9-1	33-23-12		D11570		8			SM00848		S		YC051-YL999, YR301-YR328
0848O	18		PA		9-9	33-23-12		D11570		8			SM00848		S		YN231-YN501
0849A	16		CQ		9-1	35-21-21		D11570		11			SM00849		S		YC051-YL999, YR301-YR328
0849A	16		CQ		9-11	35-21-21		D11570		11			SM00849		S		YN231-YN501
0850K	18		PA		9-1	33-27-22		D11570		10			SM00850		S		YC051-YL999, YR301-YR328
0850K	18		PA		9-11	33-27-22		D11570		10			SM00850		S		YN231-YN501
0851WY	18		PA		7-6	33-25-22		D11572		1			SM00861		S		YC051-YL999, YR301-YR328
0851WY	18		PA		8-0	33-25-22		D11572		1			SM00861		S		YN231-YN501
0852WV	22		PA		7-6	33-27-22		D11572		2			SM00862		S		YC051-YL999, YR301-YR328
0852WV	22		PA		7-11	33-27-22		D11572		2			SM00862		S		YN231-YN501
0853WG	22		PA		7-6	33-27-22		D11572		3			SM00863		S		YC051-YL999, YR301-YR328
0853WG	22		PA		7-11	33-27-22		D11572		3			SM00863		S		YN231-YN501
0854WO	22		PA		7-6	33-27-22		D11572		4			SM00864		S		YC051-YL999, YR301-YR328
0854WO	22		PA		7-11	33-27-22		D11572		4			SM00864		S		YN231-YN501
0855V	22		PA		7-6	33-27-22		D11572		5			SM00865		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3150

Page 38

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
0855V	22		PA		7-11	33-27-22	D11572				SM00865		S		YN231-YN501
0856N	18		PA		7-6	33-23-12	D11572				SM00866		S		YC051-YL999, YR301-YR328
0856N	18		PA		8-0	33-23-12	D11572				SM00866		S		YN231-YN501
0857W	20		PA		7-6	33-25-22	D11572				SM00867		S		YC051-YL999, YR301-YR328
0857W	20		PA		8-0	33-25-22	D11572				SM00867		S		YN231-YN501
0858O	18		PA		7-6	33-23-12	D11572				SM00868		S		YC051-YL999, YR301-YR328
0858O	18		PA		8-0	33-23-12	D11572				SM00868		S		YN231-YN501
0859A	16		CQ		7-6	35-21-21	D11572				SM00869		S		YC051-YL999, YR301-YR328
0859A	16		CQ		7-11	35-21-21	D11572				SM00869		S		YN231-YN501
0860K	18		PA		7-6	33-27-22	D11572				SM00870		S		YC051-YL999, YR301-YR328
0860K	18		PA		7-11	33-27-22	D11572				SM00870		S		YN231-YN501
0861WY	18		PA		9-8	33-25-22	D11574				SM00861		S		YC051-YL999, YR301-YR328
0862WV	22		PA		9-8	33-27-22	D11574				SM00862		S		YC051-YL999, YR301-YR328
0863WG	22		PA		9-8	33-27-22	D11574				SM00863		S		YC051-YL999, YR301-YR328
0864WO	22		PA		9-8	33-27-22	D11574				SM00864		S		YC051-YL999, YR301-YR328
0865V	22		PA		9-8	33-27-22	D11574				SM00865		S		YC051-YL999, YR301-YR328
0866N	18		PA		9-8	33-23-12	D11574				SM00866		S		YC051-YL999, YR301-YR328
0867W	20		PA		9-8	33-25-22	D11574				SM00867		S		YC051-YL999, YR301-YR328
0868O	18		PA		9-8	33-23-12	D11574				SM00868		S		YC051-YL999, YR301-YR328
0869A	16		CQ		9-8	35-21-21	D11574				SM00869		S		YC051-YL999, YR301-YR328
0870K	18		PA		9-8	33-27-22	D11574				SM00870		S		YC051-YL999, YR301-YR328
0871WY	18		PA		7-0	33-25-22	D11576				SM00881		S		YC051-YL999, YR301-YR328
0871WY	18		PA		9-10	33-25-22	D11576				SM00861		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 39

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
0872WV	22		PA		7-0	33-27-22	D11576		2		SM00882		S		YC051-YL999, YR301-YR328
0872WV	22		PA		10-3	33-27-22	D11576		2		SM00862		S		YN231-YN501
0873WG	22		PA		7-0	33-27-22	D11576		3		SM00883		S		YC051-YL999, YR301-YR328
0873WG	22		PA		10-3	33-27-22	D11576		3		SM00863		S		YN231-YN501
0874WO	22		PA		7-0	33-27-22	D11576		4		SM00884		S		YC051-YL999, YR301-YR328
0874WO	22		PA		10-3	33-27-22	D11576		4		SM00864		S		YN231-YN501
0875V	22		PA		7-0	33-27-22	D11576		5		SM00885		S		YC051-YL999, YR301-YR328
0875V	22		PA		10-3	33-27-22	D11576		5		SM00865		S		YN231-YN501
0876N	18		PA		7-0	33-23-12	D11576		6		SM00886		S		YC051-YL999, YR301-YR328
0876N	18		PA		9-10	33-23-12	D11576		6		SM00866		S		YN231-YN501
0877W	20		PA		7-0	33-25-22	D11576		7		SM00887		S		YC051-YL999, YR301-YR328
0877W	20		PA		9-10	33-25-22	D11576		7		SM00867		S		YN231-YN501
0878O	18		PA		7-0	33-23-12	D11576		8		SM00888		S		YC051-YL999, YR301-YR328
0878O	18		PA		9-10	33-23-12	D11576		8		SM00868		S		YN231-YN501
0879A	16		CQ		7-0	35-21-21	D11576		11		SM00889		S		YC051-YL999, YR301-YR328
0879A	16		CQ		10-3	35-21-21	D11576		11		SM00869		S		YN231-YN501
0880K	18		PA		7-0	33-27-22	D11576		10		SM00890		S		YC051-YL999, YR301-YR328
0880K	18		PA		10-3	33-27-22	D11576		10		SM00870		S		YN231-YN501
0881WY	18		PA		8-9	33-25-22	D11578		1		SM00881		S		YC051-YL999, YR301-YR328
0881WY	18		PA		9-5	33-25-22	D11578		1		SM00861		S		YN231-YN501
0882WV	22		PA		8-9	33-27-22	D11578		2		SM00882		S		YC051-YL999, YR301-YR328
0882WV	22		PA		10-0	33-27-22	D11578		2		SM00862		S		YN231-YN501
0883WG	22		PA		8-9	33-27-22	D11578		3		SM00883		S		YC051-YL999, YR301-YR328
0883WG	22		PA		10-0	33-27-22	D11578		3		SM00863		S		YN231-YN501
0884WO	22		PA		8-9	33-27-22	D11578		4		SM00884		S		YC051-YL999, YR301-YR328
0884WO	22		PA		10-0	33-27-22	D11578		4		SM00864		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 40

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
0885V	22		PA		8-9	33-27-22	D11578		5		SM00885		S		YC051-YL999, YR301-YR328
0885V	22		PA		10-0	33-27-22	D11578		5		SM00865		S		YN231-YN501
0886N	18		PA		8-9	33-23-12	D11578		6		SM00886		S		YC051-YL999, YR301-YR328
0886N	18		PA		9-5	33-23-12	D11578		6		SM00866		S		YN231-YN501
0887W	20		PA		8-9	33-25-22	D11578		7		SM00887		S		YC051-YL999, YR301-YR328
0887W	20		PA		9-5	33-25-22	D11578		7		SM00867		S		YN231-YN501
0888O	18		PA		8-9	33-23-12	D11578		8		SM00888		S		YC051-YL999, YR301-YR328
0888O	18		PA		9-5	33-23-12	D11578		8		SM00868		S		YN231-YN501
0889A	16		CQ		8-9	35-21-21	D11578		11		SM00889		S		YC051-YL999, YR301-YR328
0889A	16		CQ		10-0	35-21-21	D11578		11		SM00869		S		YN231-YN501
0890K	18		PA		8-9	33-27-22	D11578		10		SM00890		S		YC051-YL999, YR301-YR328
0890K	18		PA		10-0	33-27-22	D11578		10		SM00870		S		YN231-YN501
0901	20		PA		93-3	SPARE	D40198P		1		D40270P		2		YC051-YL999, YR301-YR328
0901	20		PA		74-7	SPARE	D40198P		1		D40270P		2		YN231-YN501
0902	20		PA		93-3	SPARE	D40198P		2		D40270P		3		YC051-YL999, YR301-YR328
0902	20		PA		74-7	SPARE	D40198P		2		D40270P		3		YN231-YN501
0903	20		PA		93-3	SPARE	D40198P		3		D40270P		8		YC051-YL999, YR301-YR328
0903	20		PA		74-7	SPARE	D40198P		3		D40270P		8		YN231-YN501
0904	20		PA		93-3	SPARE	D40198P		4		D40270P		9		YC051-YL999, YR301-YR328
0904	20		PA		74-7	SPARE	D40198P		4		D40270P		9		YN231-YN501
0907	20		PA		9-8	33-25-22	D40198P		7		D40108P		7		YC051-YL999, YR301-YR328
0907	20		PA		9-9	33-25-22	D40198P		7		D40108P		7		YN231-YN501
0908	20		PA		9-8	33-25-21	D40198P		8		D40108P		8		YC051-YL999, YR301-YR328
0908	20		PA		9-9	33-25-21	D40198P		8		D40108P		8		YN231-YN501
0909	18		PA		9-8	33-25-22	D40198P		9		D40108P		9		YC051-YL999, YR301-YR328
0909	18		PA		9-9	33-25-22	D40198P		9		D40108P		9		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 41

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type
W3150	286A3150			P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
0911	22	PA		11-10	33-27-21	D40198P	11			SM00505		S		YC051-YL999, YR301-YR328
0911	22	PA		10-10	33-27-21	D40198P	11			SM00505		S		YN231-YN501
0912	22	PA		11-10	33-27-21	D40198P	12			SM00502		S		YC051-YL999, YR301-YR328
0912	22	PA		10-10	33-27-21	D40198P	12			SM00502		S		YN231-YN501
0913	22	PA		11-10	33-27-21	D40198P	13			SM00503		S		YC051-YL999, YR301-YR328
0913	22	PA		10-10	33-27-21	D40198P	13			SM00503		S		YN231-YN501
0914	22	PA		8-11	33-27-11	D40198P	14			SP02990		S		YC051-YL999, YR301-YR328
0914	22	PA		9-3	33-27-11	D40198P	14			SP02990		S		YN231-YN501
0915	16	CQ		1-0	35-21-21	D40198P	15			SM00409		S		YC051-YL999, YR301-YR328
0915	16	CQ		6-8	35-21-21	D40198P	15			SM00409		S		YN231-YN501
0916	16	CQ		56-4	35-21-21	D40198P	16			SM00749		S		YC051-YL999, YR301-YR328
0916	16	CQ		44-4	35-21-21	D40198P	16			SM00709		S		YN231-YN501
0918	18	PA		9-8	33-25-11	D40198P	18			D40108P	10			YC051-YL999, YR301-YR328
0918	18	PA		9-9	33-25-11	D40198P	18			D40108P	10			YN231-YN501
0919	18	PA		9-8	33-25-21	D40198P	19			D40108P	6			YC051-YL999, YR301-YR328
0919	18	PA		9-9	33-25-21	D40198P	19			D40108P	6			YN231-YN501
0923	22	PA		6-11	33-27-21	SP02990		S		SM00504		S		YC051-YL999, YR301-YR328
0923	22	PA		5-2	33-27-21	SP02990		S		SM00504		S		YN231-YN501
0924	18	PA		4-3	33-27-21	SM00590		S		GD08010	DC..	1		YC051-YL999, YR301-YR328
0924	18	PA		4-1	33-27-21	SM00590		S		GD03870	DC..	1		YN231-YN501
0925	18	PA		2-11	33-27-22	SM00750		S		GD04004	DC..	1		YC051-YL999, YR301-YR328
0925	18	PA		2-11	33-27-22	SM00710		S		GD04004	DC..	1		YN231-YN501
0926	18	PA		6-0	33-27-22	SM00890		S		GD03990	DC..	1		YC051-YL999, YR301-YR328
0926	18	PA		3-2	33-27-22	SM00850		S		GD03990	DC..	1		YN231-YN501
0931	18	PA		4-9	33-25-21	D40104J	9			SM00501		S		YC051-YL999, YR301-YR328
0931	18	PA		6-7	33-25-21	D40104J	9			SM00501		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 42

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
0937	20		PA		4-9	33-25-21	D40104J	7			SM00507		S		YC051-YL999, YR301-YR328
0937	20		PA		6-7	33-25-21	D40104J	7			SM00507		S		YN231-YN501
0939	16		CQ		11-4	35-21-21	SM00409		S		SM00509		S		YC051-YL999, YR301-YR328
0939	16		CQ		4-9	35-21-21	SM00409		S		SM00509		S		YN231-YN501
0941	18		PA		6-7	33-25-22	D40106J	9			SM00741		S		YC051-YL999
0941	18		PA		4-2	33-25-22	D40106J	9			SM00701		S		YN231-YN260
0941	18		PA		3-5	33-25-22	D40109J	9			SM00701		S		YN501
0941	18		PA		5-5	33-25-22	D40109J	9			SM00741		S		YR301-YR328
0947	20		PA		6-7	33-25-22	D40106J	7			SM00747		S		YC051-YL999
0947	20		PA		4-2	33-25-22	D40106J	7			SM00707		S		YN231-YN260
0947	20		PA		3-5	33-25-22	D40109J	7			SM00707		S		YN501
0947	20		PA		5-5	33-25-22	D40109J	7			SM00747		S		YR301-YR328
0950	16		CQ		4-5	35-21-21	D40270P	6			SM00949		S		YC051-YL999, YR301-YR328
0950	16		CQ		4-11	35-21-21	D40270P	6			SM00869		S		YN231-YN501
0951	20		PA		4-5	33-25-22	D40270P	1			SM00947		S		YC051-YL999, YR301-YR328
0951	20		PA		4-9	33-25-22	D40270P	1			SM00867		S		YN231-YN501
0952	22		PA		4-5	33-27-22	D40270P	10			SM00942		S		YC051-YL999, YR301-YR328
0952	22		PA		4-11	33-27-22	D40270P	10			SM00862		S		YN231-YN501
0953	22		PA		4-5	33-27-22	D40270P	11			SM00943		S		YC051-YL999, YR301-YR328
0953	22		PA		4-11	33-27-22	D40270P	11			SM00863		S		YN231-YN501
0955	22		PA		4-5	33-27-22	D40270P	5			SM00945		S		YC051-YL999, YR301-YR328
0955	22		PA		4-11	33-27-22	D40270P	5			SM00865		S		YN231-YN501
0957	18		PA		4-5	33-25-22	D40270P	4			SM00941		S		YC051-YL999, YR301-YR328
0957	18		PA		4-9	33-25-22	D40270P	4			SM00861		S		YN231-YN501
2001B	22		PB	GA	7-7	23-31-02	D11500	14			SM00514		S		YC051-YL999, YR301-YR328
2001B	22		PB	GA	6-4	23-31-02	D11500	14			SM00514		S		YN231-YN501
2001R	22		PB	GA	0-0	23-31-02	D11500	13			SM00513		S		ALL
2011B	22		PB	GK	8-10	23-31-02	D11502	14			SM00514		S		YC051-YL999, YR301-YR328
2011B	22		PB	GK	7-1	23-31-02	D11502	14			SM00514		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 43

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150			P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
2011R	22	PB	GK		0-0	23-31-02	D11502	13			SM00513		S		ALL
2013B	22	PB	GM		2-7	23-31-02	SM00514		S		SM00534		S		YC051-YL999, YR301-YR328
2013B	22	PB	GM		3-9	23-31-02	SM00514		S		SM00534		S		YN231-YN501
2013R	22	PB	GM		0-0	23-31-02	SM00513		S		SM00533		S		ALL
2021B	22	PB	GV		9-1	23-31-02	D11504	14			SM00534		S		YC051-YL999, YR301-YR328
2021B	22	PB	GV		7-2	23-31-02	D11504	14			SM00534		S		YN231-YN501
2021R	22	PB	GV		0-0	23-31-02	D11504	13			SM00533		S		ALL
2031B	22	PB	HF		8-8	23-31-02	D11506	14			SM00534		S		YC051-YL999, YR301-YR328
2031B	22	PB	HF		7-3	23-31-02	D11506	14			SM00534		S		YN231-YN501
2031R	22	PB	HF		0-0	23-31-02	D11506	13			SM00533		S		ALL
2033B	22	PB	HH		3-9	23-31-02	SM00534		S		SM00554		S		YC051-YL999, YR301-YR328
2033B	22	PB	HH		3-10	23-31-02	SM00534		S		SM00554		S		YN231-YN501
2033R	22	PB	HH		0-0	23-31-02	SM00533		S		SM00553		S		ALL
2041B	22	PB	HQ		7-6	23-31-02	D11508	14			SM00554		S		YC051-YL999, YR301-YR328
2041B	22	PB	HQ		7-4	23-31-02	D11508	14			SM00554		S		YN231-YN501
2041R	22	PB	HQ		0-0	23-31-02	D11508	13			SM00553		S		ALL
2051B	22	PB	IA		8-9	23-31-02	D11510	14			SM00554		S		YC051-YL999, YR301-YR328
2051B	22	PB	IA		7-3	23-31-02	D11510	14			SM00554		S		YN231-YN501
2051R	22	PB	IA		0-0	23-31-02	D11510	13			SM00553		S		ALL
2053B	22	PB	IC		3-11	23-31-02	SM00554		S		SM00574		S		ALL
2053R	22	PB	IC		0-0	23-31-02	SM00553		S		SM00573		S		ALL
2061B	22	PB	IK		8-3	23-31-02	D11512	14			SM00574		S		YC051-YL999, YR301-YR328
2061B	22	PB	IK		8-5	23-31-02	D11512	14			SM00574		S		YN231-YN501
2061R	22	PB	IK		0-0	23-31-02	D11512	13			SM00573		S		ALL
2071B	22	PB	IV		9-9	23-31-02	D11514	14			SM00574		S		YC051-YL999, YR301-YR328
2071B	22	PB	IV		8-10	23-31-02	D11514	14			SM00574		S		YN231-YN501
2071R	22	PB	IV		0-0	23-31-02	D11514	13			SM00573		S		ALL
2073B	22	PB	IX		6-4	23-31-02	SM00574		S		SM00594		S		YC051-YL999, YR301-YR328
2073B	22	PB	IX		2-3	23-31-02	SM00574		S		SM00594		S		YN231-YN501
2073R	22	PB	IX		0-0	23-31-02	SM00573		S		SM00593		S		ALL

WIRE LIST

D280A108

91-21-11

Section W3150

Page 44

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150			P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
2081B	22	PB	JF		8-10	23-31-02	D11516	14			SM00594		S		YC051-YL999, YR301-YR328
2081B	22	PB	JF		9-0	23-31-02	D11516	14			SM00594		S		YN231-YN501
2081R	22	PB	JF		0-0	23-31-02	D11516	13			SM00593		S		ALL
2091B	22	PB	JQ		8-5	23-31-02	D11518	14			SM00594		S		YC051-YL999, YR301-YR328
2091B	22	PB	JQ		11-10	23-31-02	D11518	14			SM00594		S		YN231-YN501
2091R	22	PB	JQ		0-0	23-31-02	D11518	13			SM00593		S		ALL
2093B	22	PB	JS		4-3	23-31-02	SM00594		S		SM00614		S		YC051-YL999, YR301-YR328
2093B	22	PB	JS		7-9	23-31-02	SM00594		S		SM00654		S		YN231-YN501
2093R	22	PB	JS		0-0	23-31-02	SM00593		S		SM00613		S		YC051-YL999, YR301-YR328
2093R	22	PB	JS		0-0	23-31-02	SM00593		S		SM00653		S		YN231-YN501
2201B	22	PB	KA		8-11	23-31-02	D11520	14			SM00614		S		YC051-YL999, YR301-YR328
2201B	22	PB	KA		8-0	23-31-02	D11520	14			SM00654		S		YN231-YN501
2201R	22	PB	KA		0-0	23-31-02	D11520	13			SM00613		S		YC051-YL999, YR301-YR328
2201R	22	PB	KA		0-0	23-31-02	D11520	13			SM00653		S		YN231-YN501
2211B	22	PB	KK		8-3	23-31-02	D11522	14			SM00614		S		YC051-YL999, YR301-YR328
2211R	22	PB	KK		0-0	23-31-02	D11522	13			SM00613		S		YC051-YL999, YR301-YR328
2213B	22	PB	KM		4-3	23-31-02	SM00614		S		SM00634		S		YC051-YL999, YR301-YR328
2213R	22	PB	KM		0-0	23-31-02	SM00613		S		SM00633		S		YC051-YL999, YR301-YR328
2221B	22	PB	KV		8-10	23-31-02	D11524	14			SM00634		S		YC051-YL999, YR301-YR328
2221R	22	PB	KV		0-0	23-31-02	D11524	13			SM00633		S		YC051-YL999, YR301-YR328
2231B	22	PB	LF		7-9	23-31-02	D11526	14			SM00634		S		YC051-YL999, YR301-YR328
2231R	22	PB	LF		0-0	23-31-02	D11526	13			SM00633		S		YC051-YL999, YR301-YR328
2233B	22	PB	LH		4-3	23-31-02	SM00634		S		SM00654		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3150

Page 45

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W3150	286A3150			P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
2233R	22		PB	LH	0-0	23-31-02	SM00633		S		SM00653		S	YC051-YL999, YR301-YR328
2241B	22		PB	LQ	10-7	23-31-02	D11528		14		SM00654		S	YC051-YL999, YR301-YR328
2241R	22		PB	LQ	0-0	23-31-02	D11528		13		SM00653		S	YC051-YL999, YR301-YR328
2251B	22		PB	MA	10-1	23-31-02	D11530		14		SM00654		S	YC051-YL999, YR301-YR328
2251B	22		PB	MA	10-7	23-31-02	D11530		14		SM00654		S	YN231-YN501
2251R	22		PB	MA	0-0	23-31-02	D11530		13		SM00653		S	ALL
2253B	22		PB	MC	6-3	23-31-02	SM00654		S		SM00674		S	YC051-YL999, YR301-YR328
2253B	22		PB	MC	9-4	23-31-02	SM00654		S		SM00674		S	YN231-YN501
2253R	22		PB	MC	0-0	23-31-02	SM00653		S		SM00673		S	ALL
2261B	22		PB	MK	8-0	23-31-02	D11532		14		SM00674		S	YC051-YL999, YR301-YR328
2261B	22		PB	MK	10-0	23-31-02	D11532		14		SM00654		S	YN231-YN501
2261R	22		PB	MK	0-0	23-31-02	D11532		13		SM00673		S	YC051-YL999, YR301-YR328
2261R	22		PB	MK	0-0	23-31-02	D11532		13		SM00653		S	YN231-YN501
2271B	22		PB	MV	8-4	23-31-02	D11534		14		SM00674		S	YC051-YL999, YR301-YR328
2271B	22		PB	MV	7-3	23-31-02	D11534		14		SM00674		S	YN231-YN501
2271R	22		PB	MV	0-0	23-31-02	D11534		13		SM00673		S	ALL
2273B	22		PB	MX	3-9	23-31-02	SM00674		S		SM00694		S	YC051-YL999, YR301-YR328
2273B	22		PB	MX	4-4	23-31-02	SM00674		S		SM00694		S	YN231-YN501
2273R	22		PB	MX	0-0	23-31-02	SM00673		S		SM00693		S	ALL
2281B	22		PB	NF	9-0	23-31-02	D11536		14		SM00694		S	YC051-YL999, YR301-YR328
2281B	22		PB	NF	7-4	23-31-02	D11536		14		SM00674		S	YN231-YN501
2281R	22		PB	NF	0-0	23-31-02	D11536		13		SM00693		S	YC051-YL999, YR301-YR328
2281R	22		PB	NF	0-0	23-31-02	D11536		13		SM00673		S	YN231-YN501
2291B	22		PB	NQ	9-3	23-31-02	D11538		14		SM00694		S	YC051-YL999, YR301-YR328
2291B	22		PB	NQ	8-1	23-31-02	D11538		14		SM00694		S	YN231-YN501
2291R	22		PB	NQ	0-0	23-31-02	D11538		13		SM00693		S	ALL

WIRE LIST

D280A108

91-21-11

Section W3150

Page 46

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
2293B	22	PB	NS		3-9	23-31-02	SM00694		S		SM00714		S		YC051-YL999, YR301-YR328
2293B	22	PB	NS		3-7	23-31-02	SM00694		S		SM00714		S		YN231-YN501
2293R	22	PB	NS		0-0	23-31-02	SM00693		S		SM00713		S		ALL
2401B	22	PB	OA		9-3	23-31-02	D11540	14			SM00714		S		YC051-YL999, YR301-YR328
2401B	22	PB	OA		9-2	23-31-02	D11540	14			SM00694		S		YN231-YN501
2401R	22	PB	OA		0-0	23-31-02	D11540	13			SM00713		S		YC051-YL999, YR301-YR328
2401R	22	PB	OA		0-0	23-31-02	D11540	13			SM00693		S		YN231-YN501
2411B	22	PB	OK		7-10	23-31-02	D11542	14			SM00714		S		YC051-YL999, YR301-YR328
2411B	22	PB	OK		9-5	23-31-02	D11542	14			SM00714		S		YN231-YN501
2411R	22	PB	OK		0-0	23-31-02	D11542	13			SM00713		S		ALL
2413B	22	PB	OM		2-5	23-31-02	SM00714		S		SM00734		S		YC051-YL999, YR301-YR328
2413B	22	PB	OM		8-2	23-31-02	SM00714		S		SM00734		S		YN231-YN501
2413R	22	PB	OM		0-0	23-31-02	SM00713		S		SM00733		S		ALL
2421B	22	PB	OV		8-5	23-31-02	D11544	14			SM00734		S		YC051-YL999, YR301-YR328
2421B	22	PB	OV		12-0	23-31-02	D11544	14			SM00714		S		YN231-YN501
2421R	22	PB	OV		0-0	23-31-02	D11544	13			SM00733		S		YC051-YL999, YR301-YR328
2421R	22	PB	OV		0-0	23-31-02	D11544	13			SM00713		S		YN231-YN501
2431B	22	PB	PF		10-4	23-31-02	D11546	14			SM00734		S		YC051-YL999, YR301-YR328
2431B	22	PB	PF		9-11	23-31-02	D11546	14			SM00734		S		YN231-YN501
2431R	22	PB	PF		0-0	23-31-02	D11546	13			SM00733		S		ALL
2433B	22	PB	PH		6-8	23-31-02	SM00734		S		SM00754		S		YC051-YL999, YR301-YR328
2433B	22	PB	PH		4-0	23-31-02	SM00734		S		SM00754		S		YN231-YN501
2433R	22	PB	PH		0-0	23-31-02	SM00733		S		SM00753		S		ALL
2441B	22	PB	PQ		8-8	23-31-02	D11548	14			SM00754		S		YC051-YL999, YR301-YR328
2441B	22	PB	PQ		9-4	23-31-02	D11548	14			SM00734		S		YN231-YN501
2441R	22	PB	PQ		0-0	23-31-02	D11548	13			SM00753		S		YC051-YL999, YR301-YR328
2441R	22	PB	PQ		0-0	23-31-02	D11548	13			SM00733		S		YN231-YN501

WIRE LIST

D280A108

91-21-11
Section W3150
Page 47
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W3150	286A3150			P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
2451B	22		PB	QA	8-8	23-31-02	D11550	14		SM00754		S		YC051-YL999, YR301-YR328	
2451B	22		PB	QA	8-0	23-31-02	D11550	14		SM00754		S		YN231-YN501	
2451R	22		PB	QA	0-0	23-31-02	D11550	13		SM00753		S		ALL	
2453B	22		PB	QC	4-0	23-31-02	SM00754		S	SM00774		S		YC051-YL999, YR301-YR328	
2453B	22		PB	QC	3-6	23-31-02	SM00754		S	SM00834		S		YN231-YN501	
2453R	22		PB	QC	0-0	23-31-02	SM00753		S	SM00773		S		YC051-YL999, YR301-YR328	
2453R	22		PB	QC	0-0	23-31-02	SM00753		S	SM00833		S		YN231-YN501	
2461B	22		PB	QK	8-5	23-31-02	D11552	14		SM00774		S		YC051-YL999, YR301-YR328	
2461B	22		PB	QK	8-11	23-31-02	D11552	14		SM00754		S		YN231-YN501	
2461R	22		PB	QK	0-0	23-31-02	D11552	13		SM00773		S		YC051-YL999, YR301-YR328	
2461R	22		PB	QK	0-0	23-31-02	D11552	13		SM00753		S		YN231-YN501	
2471B	22		PB	QV	7-8	23-31-02	D11554	14		SM00774		S		YC051-YL999, YR301-YR328	
2471R	22		PB	QV	0-0	23-31-02	D11554	13		SM00773		S		YC051-YL999, YR301-YR328	
2473B	22		PB	QX	2-7	23-31-02	SM00774		S	SM00794		S		YC051-YL999, YR301-YR328	
2473R	22		PB	QX	0-0	23-31-02	SM00773		S	SM00793		S		YC051-YL999, YR301-YR328	
2481B	22		PB	RF	7-2	23-31-02	D11556	14		SM00794		S		YC051-YL999, YR301-YR328	
2481R	22		PB	RF	0-0	23-31-02	D11556	13		SM00793		S		YC051-YL999, YR301-YR328	
2491B	22		PB	RQ	8-9	23-31-02	D11558	14		SM00794		S		YC051-YL999, YR301-YR328	
2491R	22		PB	RQ	0-0	23-31-02	D11558	13		SM00793		S		YC051-YL999, YR301-YR328	
2493B	22		PB	RS	3-9	23-31-02	SM00794		S	SM00814		S		YC051-YL999, YR301-YR328	
2493R	22		PB	RS	0-0	23-31-02	SM00793		S	SM00813		S		YC051-YL999, YR301-YR328	
2601B	22		PB	SA	7-9	23-31-02	D11560	14		SM00814		S		YC051-YL999, YR301-YR328	

WIRE LIST

D280A108

91-21-11

Section W3150

Page 48

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
2601R	22	PB	SA		0-0	23-31-02	D11560	13			SM00813		S		YC051-YL999, YR301-YR328
2611B	22	PB	SK		9-4	23-31-02	D11562	14			SM00814		S		YC051-YL999, YR301-YR328
2611R	22	PB	SK		0-0	23-31-02	D11562	13			SM00813		S		YC051-YL999, YR301-YR328
2613B	22	PB	SM		4-3	23-31-02	SM00814		S		SM00834		S		YC051-YL999, YR301-YR328
2613R	22	PB	SM		0-0	23-31-02	SM00813		S		SM00833		S		YC051-YL999, YR301-YR328
2621B	22	PB	SV		7-10	23-31-02	D11564	14			SM00834		S		YC051-YL999, YR301-YR328
2621B	22	PB	SV		9-3	23-31-02	D11564	14			SM00834		S		YN231-YN501
2621R	22	PB	SV		0-0	23-31-02	D11564	13			SM00833		S		ALL
2631B	22	PB	TF		9-4	23-31-02	D11566	14			SM00834		S		YC051-YL999, YR301-YR328
2631B	22	PB	TF		14-10	23-31-02	D11566	14			SM00834		S		YN231-YN501
2631R	22	PB	TF		0-0	23-31-02	D11566	13			SM00833		S		ALL
2633B	22	PB	TH		4-3	23-31-02	SM00834		S		SM00854		S		YC051-YL999, YR301-YR328
2633B	22	PB	TH		8-1	23-31-02	SM00834		S		SM00854		S		YN231-YN501
2633R	22	PB	TH		0-0	23-31-02	SM00833		S		SM00853		S		ALL
2641B	22	PB	TQ		8-3	23-31-02	D11568	14			SM00854		S		YC051-YL999, YR301-YR328
2641B	22	PB	TQ		8-11	23-31-02	D11568	14			SM00854		S		YN231-YN501
2641R	22	PB	TQ		0-0	23-31-02	D11568	13			SM00853		S		ALL
2651B	22	PB	UA		9-1	23-31-02	D11570	14			SM00854		S		YC051-YL999, YR301-YR328
2651B	22	PB	UA		9-11	23-31-02	D11570	14			SM00854		S		YN231-YN501
2651R	22	PB	UA		0-0	23-31-02	D11570	13			SM00853		S		ALL
2653B	22	PB	UC		4-1	23-31-02	SM00854		S		SM00874		S		YC051-YL999, YR301-YR328
2653B	22	PB	UC		5-4	23-31-02	SM00854		S		SM00874		S		YN231-YN501
2653R	22	PB	UC		0-0	23-31-02	SM00853		S		SM00873		S		ALL
2661B	22	PB	UK		7-6	23-31-02	D11572	14			SM00874		S		YC051-YL999, YR301-YR328
2661B	22	PB	UK		7-11	23-31-02	D11572	14			SM00874		S		YN231-YN501
2661R	22	PB	UK		0-0	23-31-02	D11572	13			SM00873		S		ALL

WIRE LIST

D280A108

91-21-11

Section W3150

Page 49

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W3150	286A3150			P18 AND AB0340A DISC TO LEFT PSU'S (continued)										
2671B	22		PB	UV	9-8	23-31-02	D11574	14		SM00874		S		YC051-YL999, YR301-YR328
2671R	22		PB	UV	0-0	23-31-02	D11574	13		SM00873		S		YC051-YL999, YR301-YR328
2673B	22		PB	UM	4-2	23-31-02	SM00874		S	SM00894		S		YC051-YL999, YR301-YR328
2673R	22		PB	UM	0-0	23-31-02	SM00873		S	SM00893		S		YC051-YL999, YR301-YR328
2681B	22		PB	VF	7-0	23-31-02	D11576	14		SM00894		S		YC051-YL999, YR301-YR328
2681B	22		PB	VF	10-3	23-31-02	D11576	14		SM00874		S		YN231-YN501
2681R	22		PB	VF	0-0	23-31-02	D11576	13		SM00893		S		YC051-YL999, YR301-YR328
2681R	22		PB	VF	0-0	23-31-02	D11576	13		SM00873		S		YN231-YN501
2691B	22		PB	VQ	8-9	23-31-02	D11578	14		SM00894		S		YC051-YL999, YR301-YR328
2691B	22		PB	VQ	10-0	23-31-02	D11578	14		SM00874		S		YN231-YN501
2691R	22		PB	VQ	0-0	23-31-02	D11578	13		SM00893		S		YC051-YL999, YR301-YR328
2691R	22		PB	VQ	0-0	23-31-02	D11578	13		SM00873		S		YN231-YN501
2692B	18		PB	VR	4-9	33-23-11	SM00508		S	D40104J	2			YC051-YL999, YR301-YR328
2692B	18		PB	VR	6-7	33-23-11	SM00508		S	D40104J	2			YN231-YN501
2692R	18		PB	VR	0-0	33-23-11	D40104J	1		SM00506		S		ALL
2693B	18		PB	VS	7-5	33-23-11	SM00568		S	D40104J	12			YC051-YL999, YR301-YR328
2693B	18		PB	VS	7-6	33-23-11	SM00568		S	D40104J	12			YN231-YN501
2693R	18		PB	VS	0-0	33-23-11	D40104J	6		SM00566		S		ALL
2694B	18		PB	VT	20-1	33-23-11	SM00628		S	D40104J	3			YC051-YL999, YR301-YR328
2694B	18		PB	VT	15-11	33-23-11	SM00648		S	D40104J	3			YN231-YN501
2694R	18		PB	VT	0-0	33-23-11	D40104J	8		SM00626		S		YC051-YL999, YR301-YR328
2694R	18		PB	VT	0-0	33-23-11	D40104J	8		SM00646		S		YN231-YN501
2695B	18		PB	VU	32-2	33-23-11	SM00688		S	D40104J	14			YC051-YL999, YR301-YR328
2695B	18		PB	VU	24-2	33-23-11	SM00668		S	D40104J	14			YN231-YN501
2695R	18		PB	VU	0-0	33-23-11	D40104J	13		SM00686		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3150

Page 50

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150			P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
2695R	18	PB	VU		0-0	33-23-11	D40104J	13			SM00666		S		YN231-YN501
2696B	18	PB	VV		6-7	33-23-12	SM00748		S		D40106J	2			YC051-YL999
2696B	18	PB	VV		4-2	33-23-12	SM00708		S		D40106J	2			YN231-YN260
2696B	18	PB	VV		3-5	33-23-12	SM00708		S		D40109J	2			YN501
2696B	18	PB	VV		5-5	33-23-12	SM00748		S		D40109J	2			YR301-YR328
2696R	18	PB	VV		0-0	33-23-12	D40106J	1			SM00746		S		YC051-YL999
2696R	18	PB	VV		0-0	33-23-12	D40106J	1			SM00706		S		YN231-YN260
2696R	18	PB	VV		0-0	33-23-12	D40109J	1			SM00706		S		YN501
2696R	18	PB	VV		0-0	33-23-12	D40109J	1			SM00746		S		YR301-YR328
2697B	18	PB	VW		15-3	33-23-12	SM00808		S		D40106J	12			YC051-YL999
2697B	18	PB	VW		15-3	33-23-12	SM00748		S		D40106J	12			YN231-YN260
2697B	18	PB	VW		14-7	33-23-12	SM00748		S		D40109J	12			YN501
2697B	18	PB	VW		14-6	33-23-12	SM00808		S		D40109J	12			YR301-YR328
2697R	18	PB	VW		0-0	33-23-12	D40106J	6			SM00806		S		YC051-YL999
2697R	18	PB	VW		0-0	33-23-12	D40106J	6			SM00746		S		YN231-YN260
2697R	18	PB	VW		0-0	33-23-12	D40109J	6			SM00746		S		YN501
2697R	18	PB	VW		0-0	33-23-12	D40109J	6			SM00806		S		YR301-YR328
2698B	18	PB	VX		22-7	33-23-12	D40106J	3			SM00848		S		YC051-YL999
2698B	18	PB	VX		25-3	33-23-12	SM00848		S		D40106J	3			YN231-YN260
2698B	18	PB	VX		24-7	33-23-12	SM00848		S		D40109J	3			YN501
2698B	18	PB	VX		21-11	33-23-12	D40109J	3			SM00848		S		YR301-YR328
2698R	18	PB	VX		0-0	33-23-12	D40106J	8			SM00846		S		YC051-YN260
2698R	18	PB	VX		0-0	33-23-12	D40109J	8			SM00846		S		YN501-YR328
2699B	22	PB	VY		6-11	23-31-02	SP00135		S		SM00514		S		YC051-YL999, YR301-YR328
2699B	22	PB	VY		5-2	23-31-02	SP00135		S		SM00514		S		YN231-YN501
2699R	22	PB	VY		0-0	23-31-02	SP00133		S		SM00513		S		ALL
2700B	22	PB	VZ		4-5	23-31-02	D40270P	16			SM00954		S		YC051-YL999, YR301-YR328
2700B	22	PB	VZ		4-11	23-31-02	D40270P	16			SM00874		S		YN231-YN501
2700R	22	PB	VZ		0-0	23-31-02	D40270P	15			SM00953		S		YC051-YL999, YR301-YR328
2700R	22	PB	VZ		0-0	23-31-02	D40270P	15			SM00873		S		YN231-YN501
2701B	22	PB	V1		8-3	23-31-02	D11580	14			SM00914		S		YC051-YL999, YR301-YR328
2701R	22	PB	V1		0-0	23-31-02	D11580	13			SM00913		S		YC051-YL999, YR301-YR328
2703B	22	PB	V3		3-11	23-31-02	SM00894		S		SM00914		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3150

Page 51

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150			P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
2703R	22	PB	V3		0-0	23-31-02	SM00893		S		SM00913		S		YC051-YL999, YR301-YR328
2711B	22	PB	U1		9-5	23-31-02	D11582	14			SM00914		S		YC051-YL999, YR301-YR328
2711R	22	PB	U1		0-0	23-31-02	D11582	13			SM00913		S		YC051-YL999, YR301-YR328
2721B	22	PB	W1		6-9	23-31-02	D11584	14			SM00934		S		YC051-YL999, YR301-YR328
2721R	22	PB	W1		0-0	23-31-02	D11584	13			SM00933		S		YC051-YL999, YR301-YR328
2723B	22	PB	W3		3-11	23-31-02	SM00914		S		SM00934		S		YC051-YL999, YR301-YR328
2723R	22	PB	W3		0-0	23-31-02	SM00913		S		SM00933		S		YC051-YL999, YR301-YR328
2731B	22	PB	X1		9-8	23-31-02	D11586	14			SM00934		S		YC051-YL999, YR301-YR328
2731R	22	PB	X1		0-0	23-31-02	D11586	13			SM00933		S		YC051-YL999, YR301-YR328
2741B	22	PB	Y1		10-1	23-31-02	D11588	14			SM00954		S		YC051-YL999, YR301-YR328
2741R	22	PB	Y1		0-0	23-31-02	D11588	13			SM00953		S		YC051-YL999, YR301-YR328
2743B	22	PB	Y3		3-10	23-31-02	SM00934		S		SM00954		S		YC051-YL999, YR301-YR328
2743R	22	PB	Y3		0-0	23-31-02	SM00933		S		SM00953		S		YC051-YL999, YR301-YR328
2751B	22	PB	Z1		10-7	23-31-02	D11590	14			SM00954		S		YC051-YL999, YR301-YR328
2751R	22	PB	Z1		0-0	23-31-02	D11590	13			SM00953		S		YC051-YL999, YR301-YR328
2801B	18	PB	V8		29-8	33-23-12	D40106J	15			SM00888		S		YC051-YL999
2801B	18	PB	V8		29-0	33-23-12	D40109J	15			SM00888		S		YR301-YR328
2801R	18	PB	V8		0-0	33-23-12	D40106J	4			SM00886		S		YC051-YL999
2801R	18	PB	V8		0-0	33-23-12	D40109J	4			SM00886		S		YR301-YR328
2802B	18	PB	W8		36-5	33-23-12	D40106J	14			SM00928		S		YC051-YL999
2802B	18	PB	W8		35-8	33-23-12	D40109J	14			SM00928		S		YR301-YR328
2802R	18	PB	W8		0-0	33-23-12	D40106J	13			SM00926		S		YC051-YL999
2802R	18	PB	W8		0-0	33-23-12	D40109J	13			SM00926		S		YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3150

Page 52

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150			P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
5501WY	18		PA		3-11	33-25-22	SM00901		S		SM00921		S		YC051-YL999, YR301-YR328
5502WV	22		PA		3-11	33-27-22	SM00902		S		SM00922		S		YC051-YL999, YR301-YR328
5503WG	22		PA		3-11	33-27-22	SM00903		S		SM00923		S		YC051-YL999, YR301-YR328
5504WO	22		PA		3-11	33-27-22	SM00904		S		SM00924		S		YC051-YL999, YR301-YR328
5505V	22		PA		3-11	33-27-22	SM00905		S		SM00925		S		YC051-YL999, YR301-YR328
5507W	20		PA		3-11	33-25-22	SM00907		S		SM00927		S		YC051-YL999, YR301-YR328
5509A	16		CQ		3-11	35-21-21	SM00909		S		SM00929		S		YC051-YL999, YR301-YR328
5510K	18		PA		3-11	33-27-22	SM00910		S		SM00930		S		YC051-YL999, YR301-YR328
5521WY	18		PA		3-10	33-25-22	SM00921		S		SM00941		S		YC051-YL999, YR301-YR328
5522WV	22		PA		3-10	33-27-22	SM00922		S		SM00942		S		YC051-YL999, YR301-YR328
5523WG	22		PA		3-10	33-27-22	SM00923		S		SM00943		S		YC051-YL999, YR301-YR328
5524WO	22		PA		3-10	33-27-22	SM00924		S		SM00944		S		YC051-YL999, YR301-YR328
5525V	22		PA		3-10	33-27-22	SM00925		S		SM00945		S		YC051-YL999, YR301-YR328
5526N	18		PA		3-10	33-23-12	SM00926		S		SM00946		S		YC051-YL999, YR301-YR328
5527W	20		PA		3-10	33-25-22	SM00927		S		SM00947		S		YC051-YL999, YR301-YR328
5528O	18		PA		3-10	33-23-12	SM00928		S		SM00948		S		YC051-YL999, YR301-YR328
5529A	16		CQ		3-10	35-21-21	SM00929		S		SM00949		S		YC051-YL999, YR301-YR328
5530K	18		PA		3-10	33-27-22	SM00930		S		SM00950		S		YC051-YL999, YR301-YR328
5601WY	18		PA		8-3	33-25-22	D11580		1		SM00901		S		YC051-YL999, YR301-YR328

WIRE LIST
D280A108

91-21-11
Section W3150
Page 53
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150			P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
5602WV	22		PA		8-3	33-27-22	D11580		2		SM00902		S		YC051-YL999, YR301-YR328
5603WG	22		PA		8-3	33-27-22	D11580		3		SM00903		S		YC051-YL999, YR301-YR328
5604WO	22		PA		8-3	33-27-22	D11580		4		SM00904		S		YC051-YL999, YR301-YR328
5605V	22		PA		8-3	33-27-22	D11580		5		SM00905		S		YC051-YL999, YR301-YR328
5606N	18		PA		8-3	33-23-12	D11580		6		SM00906		S		YC051-YL999, YR301-YR328
5607W	20		PA		8-3	33-25-22	D11580		7		SM00907		S		YC051-YL999, YR301-YR328
5608O	18		PA		8-3	33-23-12	D11580		8		SM00908		S		YC051-YL999, YR301-YR328
5609A	16		CQ		8-3	35-21-21	D11580		11		SM00909		S		YC051-YL999, YR301-YR328
5610K	18		PA		8-3	33-27-22	D11580		10		SM00910		S		YC051-YL999, YR301-YR328
5611WY	18		PA		9-5	33-25-22	D11582		1		SM00901		S		YC051-YL999, YR301-YR328
5612WV	22		PA		9-5	33-27-22	D11582		2		SM00902		S		YC051-YL999, YR301-YR328
5613WG	22		PA		9-5	33-27-22	D11582		3		SM00903		S		YC051-YL999, YR301-YR328
5614WO	22		PA		9-5	33-27-22	D11582		4		SM00904		S		YC051-YL999, YR301-YR328
5615V	22		PA		9-5	33-27-22	D11582		5		SM00905		S		YC051-YL999, YR301-YR328
5616N	18		PA		9-5	33-23-12	D11582		6		SM00906		S		YC051-YL999, YR301-YR328
5617W	20		PA		9-5	33-25-22	D11582		7		SM00907		S		YC051-YL999, YR301-YR328
5618O	18		PA		9-5	33-23-12	D11582		8		SM00908		S		YC051-YL999, YR301-YR328
5619A	16		CQ		9-5	35-21-21	D11582		11		SM00909		S		YC051-YL999, YR301-YR328
5620K	18		PA		9-5	33-27-22	D11582		10		SM00910		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3150

Page 54

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150			P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
5621WY	18		PA		6-9	33-25-22	D11584		1		SM00921		S		YC051-YL999, YR301-YR328
5622WV	22		PA		6-9	33-27-22	D11584		2		SM00922		S		YC051-YL999, YR301-YR328
5623WG	22		PA		6-9	33-27-22	D11584		3		SM00923		S		YC051-YL999, YR301-YR328
5624WO	22		PA		6-9	33-27-22	D11584		4		SM00924		S		YC051-YL999, YR301-YR328
5625V	22		PA		6-9	33-27-22	D11584		5		SM00925		S		YC051-YL999, YR301-YR328
5626N	18		PA		6-9	33-23-12	D11584		6		SM00926		S		YC051-YL999, YR301-YR328
5627W	20		PA		6-9	33-25-22	D11584		7		SM00927		S		YC051-YL999, YR301-YR328
5628O	18		PA		6-9	33-23-12	D11584		8		SM00928		S		YC051-YL999, YR301-YR328
5629A	16		CQ		6-9	35-21-21	D11584		11		SM00929		S		YC051-YL999, YR301-YR328
5630K	18		PA		6-9	33-27-22	D11584		10		SM00930		S		YC051-YL999, YR301-YR328
5631WY	18		PA		9-8	33-25-22	D11586		1		SM00921		S		YC051-YL999, YR301-YR328
5632WV	22		PA		9-8	33-27-22	D11586		2		SM00922		S		YC051-YL999, YR301-YR328
5633WG	22		PA		9-8	33-27-22	D11586		3		SM00923		S		YC051-YL999, YR301-YR328
5634WO	22		PA		9-8	33-27-22	D11586		4		SM00924		S		YC051-YL999, YR301-YR328
5635V	22		PA		9-8	33-27-22	D11586		5		SM00925		S		YC051-YL999, YR301-YR328
5636N	18		PA		9-8	33-23-12	D11586		6		SM00926		S		YC051-YL999, YR301-YR328
5637W	20		PA		9-8	33-25-22	D11586		7		SM00927		S		YC051-YL999, YR301-YR328
5638O	18		PA		9-8	33-23-12	D11586		8		SM00928		S		YC051-YL999, YR301-YR328
5639A	16		CQ		9-8	35-21-21	D11586		11		SM00929		S		YC051-YL999, YR301-YR328

WIRE LIST
D280A108

91-21-11
Section W3150
Page 55
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3150	286A3150			P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
5640K	18		PA		9-8	33-27-22	D11586	10			SM00930		S		YC051-YL999, YR301-YR328
5641WY	18		PA		10-1	33-25-22	D11588	1			SM00941		S		YC051-YL999, YR301-YR328
5642WV	22		PA		10-1	33-27-22	D11588	2			SM00942		S		YC051-YL999, YR301-YR328
5643WG	22		PA		10-1	33-27-22	D11588	3			SM00943		S		YC051-YL999, YR301-YR328
5644WO	22		PA		10-1	33-27-22	D11588	4			SM00944		S		YC051-YL999, YR301-YR328
5645V	22		PA		10-1	33-27-22	D11588	5			SM00945		S		YC051-YL999, YR301-YR328
5646N	18		PA		10-1	33-23-12	D11588	6			SM00946		S		YC051-YL999, YR301-YR328
5647W	20		PA		10-1	33-25-22	D11588	7			SM00947		S		YC051-YL999, YR301-YR328
5648O	18		PA		10-1	33-23-12	D11588	8			SM00948		S		YC051-YL999, YR301-YR328
5649A	16		CQ		10-1	35-21-21	D11588	11			SM00949		S		YC051-YL999, YR301-YR328
5650K	18		PA		10-1	33-27-22	D11588	10			SM00950		S		YC051-YL999, YR301-YR328
5651WY	18		PA		10-7	33-25-22	D11590	1			SM00941		S		YC051-YL999, YR301-YR328
5652WV	22		PA		10-7	33-27-22	D11590	2			SM00942		S		YC051-YL999, YR301-YR328
5653WG	22		PA		10-7	33-27-22	D11590	3			SM00943		S		YC051-YL999, YR301-YR328
5654WO	22		PA		10-7	33-27-22	D11590	4			SM00944		S		YC051-YL999, YR301-YR328
5655V	22		PA		10-7	33-27-22	D11590	5			SM00945		S		YC051-YL999, YR301-YR328
5656N	18		PA		10-7	33-23-12	D11590	6			SM00946		S		YC051-YL999, YR301-YR328
5657W	20		PA		10-7	33-25-22	D11590	7			SM00947		S		YC051-YL999, YR301-YR328
5658O	18		PA		10-7	33-23-12	D11590	8			SM00948		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3150

Page 56

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W3150	286A3150				P18 AND AB0340A DISC TO LEFT PSU'S (continued)											
5659A	16		CQ		10-7	35-21-21		D11590		11		SM00949		S		YC051-YL999, YR301-YR328
5660K	18		PA		10-7	33-27-22		D11590		10		SM00950		S		YC051-YL999, YR301-YR328
W3154	286A3154				P91 TO AFT GALLEY POWER											
0001	08		HA		9-0	25-31-11		D11430		A		SM00001		GX		YC051-YC055
0001	08		HA		9-2	25-31-11		D11430		A		SM00001		GX		YC056-YL999, YR301-YR328
0001	08		HA		10-0	25-31-11		D11430		A		SM00001		GX		YN231-YN501
0002	08		HA		9-0	25-31-11		D11430		B		SM00002		GX		YC051-YC055
0002	08		HA		9-2	25-31-11		D11430		B		SM00002		GX		YC056-YL999, YR301-YR328
0002	08		HA		10-0	25-31-11		D11430		B		SM00002		GX		YN231-YN501
0003	08		HA		9-0	25-31-11		D11430		C		SM00003		GX		YC051-YC055
0003	08		HA		9-2	25-31-11		D11430		C		SM00003		GX		YC056-YL999, YR301-YR328
0003	08		HA		10-0	25-31-11		D11430		C		SM00003		GX		YN231-YN501
0004	06		QY		89-7	25-31-11		SM00001			GX	SM00004		GX		YC051-YL999, YR301-YR328
0004	06		QY		74-11	25-31-11		SM00001			GX	SM00004		GX		YN231-YN501
0005	06		QY		89-7	25-31-11		SM00002			GX	SM00005		GX		YC051-YL999, YR301-YR328
0005	06		QY		74-11	25-31-11		SM00002			GX	SM00005		GX		YN231-YN501
0006	06		QY		89-7	25-31-11		SM00003			GX	SM00006		GX		YC051-YL999, YR301-YR328
0006	06		QY		74-11	25-31-11		SM00003			GX	SM00006		GX		YN231-YN501
0007	08		HA		9-6	25-31-11		D03800		A		SM00004		GX		YC051-YL999, YR301-YR328
0007	08		HA		3-9	25-31-11		D03800		A		SM00004		GX		YN231-YN501
0008	08		HA		9-6	25-31-11		D03800		B		SM00005		GX		YC051-YL999, YR301-YR328
0008	08		HA		3-9	25-31-11		D03800		B		SM00005		GX		YN231-YN501
0009	08		HA		9-6	25-31-11		D03800		C		SM00006		GX		YC051-YL999, YR301-YR328
0009	08		HA		3-9	25-31-11		D03800		C		SM00006		GX		YN231-YN501
0010	08		HA		3-1	25-31-11		D03800		D		GD03956	AC..	P		YC051-YL999, YR301-YR328
0010	08		HA		2-11	25-31-11		D03800		D		GD03956	AC..	P		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 57

Nov 12/2012



WIRE LIST

91-21-11

Section W3150

Page 58

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W3158	286A3158				AB0340A DISCONNECT TO LEFT AFT OVERHEAD (continued)												
0022	18	PA			36-7	33-22-31	SM00102			S		SM00122		S		YD158-YL999	
0022	18	PA			26-8	33-22-31	SM00102			S		SM00122		S		YN231-YN260	
0030	18	PA			24-1	33-22-31	SM00122			S		D40990P	1			YD158-YD170	
0031	18	PA			1-9	33-22-21	D40112P		1			SM00121		S		YC051-YD157, YL951-YN260	
0031	18	PA			27-3	33-22-21	SM00121			S		D42010P	1			YD158-YD170	
0032	18	PA			8-9	33-22-21	D42004P		1			SM00122		S		YC051-YD157	
0032	18	PA			8-9	33-22-31	SM00122			S		D42004P	1			YD158-YD170	
0032	18	PA			8-9	33-22-31	D42004P		1			SM00122		S		YL951-YL999	
0032	18	PA			8-3	33-22-31	D42004P		1			SM00122		S		YN231-YN260	
0033	18	PA			4-10	33-22-21	SM00121			S		D40984P	1			YD158-YD170	
0041	18	PA			35-11	33-22-22	D40114P		1			SM00121		S		YC051-YD157, YL951-YL999	
0041	18	PA			29-9	33-22-22	D40994P		1			SM00121		S		YD158-YD170	
0041	18	PA			26-7	33-22-22	D40114P		1			SM00121		S		YN231-YN260	
0042	18	PA			38-10	33-22-22	D42006P		1			SM00122		S		YC051-YD151	
0042	18	PA			38-10	MULTI	D42006P		1			SM00122		S		YD152-YD157	
0042	18	PA			27-2	33-22-32	SM00122			S		D40996P	1			YD158-YD170	
0042	18	PA			38-10	33-22-32	D42006P		1			SM00122		S		YL951-YL999	
0042	18	PA			29-4	33-22-32	D42006P		1			SM00122		S		YN231-YN260	
0051	20	PA			39-6	33-25-22	D40116P		10			SM00107		S		YC051-YL999	
0051	20	PA			29-1	33-25-22	D40116P		10			SM00107		S		YN231-YN501	
0051	20	PA			38-6	33-25-22	D40116P		10			SM00107		S		YR301-YR328	
0052	18	PA			39-6	33-25-22	D40116P		9			SM00109		S		YC051-YL999	
0052	18	PA			29-1	33-25-22	D40116P		9			SM00109		S		YN231-YN501	
0052	18	PA			38-6	33-25-22	D40116P		9			SM00109		S		YR301-YR328	
0053	18	PA			85-1	33-25-11	D40116P		2			SM00110		S		YC051-YL999, YR301-YR328	
0053	18	PA			60-2	33-25-11	D40116P		2			SM00110		S		YN231-YN260	
0053	18	PA			65-6	33-25-11	D40116P		2			SM00110		S		YN501	
0061	20	PA			1-11	33-25-21	D40216J		1			SM00108		S		YC051-YL999, YN501-YR328	
0061	20	PA			7-0	33-25-21	D40216J		1			SM00108		S		YN231-YN260	
0062	18	PA			1-11	33-25-21	D40216J		2			SM00106		S		YC051-YL999, YN501-YR328	
0062	18	PA			7-0	33-25-21	D40216J		2			SM00106		S		YN231-YN260	
0063	18	PA			1-11	33-25-11	D40216J		3			SM00110		S		YC051-YL999, YN501-YR328	
0063	18	PA			7-0	33-25-11	D40216J		3			SM00110		S		YN231-YN260	

WIRE LIST

D280A108

91-21-11

Section W3150

Page 59

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3158		286A3158			AB0340A DISCONNECT TO LEFT AFT OVERHEAD (continued)											
0067		16		PA		17-9	25-29-11	D40216J	7			D12100	=P	LF		YC053-YD170
0068		16		PA		12-10	25-29-11	D12100	=G	LF		GD03852	DC..	1		YC053-YD170
0087		20		PA		11-3	33-25-21	D40104P	7			SM00108		S		YC051-YL999, YR301-YR328
0087		20		PA		5-2	33-25-21	D40104P	7			SM00108		S		YN231-YN260
0087		20		PA		11-2	33-25-21	D40104P	7			SM00108		S		YN501
0089		18		PA		11-3	33-25-21	D40104P	9			SM00106		S		YC051-YL999, YR301-YR328
0089		18		PA		5-2	33-25-21	D40104P	9			SM00106		S		YN231-YN260
0089		18		PA		11-2	33-25-21	D40104P	9			SM00106		S		YN501
0097		20		PA		1-0	33-25-22	D40106P	7			SM00107		S		YC051-YL999
0097		20		PA		2-9	33-25-22	D40106P	7			SM00107		S		YN231-YN260
0097		20		PA		1-0	33-25-22	D40109P	7			SM00107		S		YN501
0097		20		PA		1-2	33-25-22	D40109P	7			SM00107		S		YR301-YR328
0099		18		PA		1-0	33-25-22	D40106P	9			SM00109		S		YC051-YL999
0099		18		PA		2-9	33-25-22	D40106P	9			SM00109		S		YN231-YN260
0099		18		PA		1-0	33-25-22	D40109P	9			SM00109		S		YN501
0099		18		PA		1-2	33-25-22	D40109P	9			SM00109		S		YR301-YR328
0101		20		PA		2-5	SPARE	D40108J	1			D40216J	4			ALL
0102		20		PA		2-5	SPARE	D40108J	2			D40216J	5			ALL
0106		18		PA		1-1	33-25-21	D40108J	6			SM00106		S		YC051-YL999, YN501-YR328
0106		18		PA		7-1	33-25-21	D40108J	6			SM00106		S		YN231-YN260
0107		20		PA		49-5	33-25-22	D40108J	7			SM00107		S		YC051-YL999
0107		20		PA		37-7	33-25-22	D40108J	7			SM00107		S		YN231-YN260
0107		20		PA		38-6	33-25-22	D40108J	7			SM00107		S		YN501
0107		20		PA		48-4	33-25-22	D40108J	7			SM00107		S		YR301-YR328
0108		20		PA		1-1	33-25-21	D40108J	8			SM00108		S		YC051-YL999, YN501-YR328
0108		20		PA		7-1	33-25-21	D40108J	8			SM00108		S		YN231-YN260
0109		18		PA		49-5	33-25-22	D40108J	9			SM00109		S		YC051-YL999
0109		18		PA		37-7	33-25-22	D40108J	9			SM00109		S		YN231-YN260
0109		18		PA		38-6	33-25-22	D40108J	9			SM00109		S		YN501
0109		18		PA		48-4	33-25-22	D40108J	9			SM00109		S		YR301-YR328
0110		18		PA		1-1	33-25-11	D40108J	10			SM00110		S		YC051-YL999, YN501-YR328
0110		18		PA		7-1	33-25-11	D40108J	10			SM00110		S		YN231-YN260
0111		20		PA		85-7	SPARE	D40108J	11			D40116P	1			YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3150

Page 60

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity			
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice	
W3158	286A3158				AB0340A DISCONNECT TO LEFT AFT OVERHEAD (continued)											
0111	20	PA		66-2	SPARE	D40108J	11			D40116P	1			YN231-YN260		
0111	20	PA		66-0	SPARE	D40108J	11			D40116P	1			YN501		
0112	20	PA		85-7	SPARE	D40108J	12			D40116P	3			YC051-YL999, YR301-YR328		
0112	20	PA		66-2	SPARE	D40108J	12			D40116P	3			YN231-YN260		
0112	20	PA		66-0	SPARE	D40108J	12			D40116P	3			YN501		
0203	20	PA		11-6	SPARE	D40102J	3			D40110P	2			YC051-YN260		
0204	20	PA		10-4	SPARE	D40102J	4			D42002P	2			YC051-YN260		
0206	18	PA		94-2	33-35-11	D40102J	6			SP04010		S		YC051-YL999, YR301-YR328		
0206	18	PA		74-9	33-35-11	D40102J	6			SP04010		S		YN231-YN260		
0206	18	PA		74-8	33-35-11	D40102J	6			SP04010		S		YN501		
0212	20	PA		85-3	SPARE	D40102J	12			D42006P	2			YC051-YD157, YL951-YL999		
0212	20	PA		73-8	SPARE	D40102J	12			D40996P	2			YD158-YD170		
0212	20	PA		65-11	SPARE	D40102J	12			D42006P	2			YN231-YN260		
0213	18	PA		11-6	33-22-21	D40102J	13			SM00101		S		YC051-YN260		
0214	18	PA		11-6	33-22-21	D40102J	14			SM00102		S		YC051-YD157		
0214	18	PA		11-6	33-22-31	D40102J	14			SM00102		S		YD158-YN260		
0225	20	PA		48-3	SPARE	D40102J	25			D40112P	2			YC051-YD157, YL951-YL999		
0225	20	PA		22-1	SPARE	D40102J	25			D42010P	2			YD158-YD170		
0225	20	PA		38-4	SPARE	D40102J	25			D40112P	2			YN231-YN260		
0226	20	PA		55-3	SPARE	D40102J	26			D42004P	2			YC051-YL999		
0226	20	PA		44-3	SPARE	D40102J	26			D42004P	2			YN231-YN260		
0228	20	PA		82-5	SPARE	D40102J	28			D40114P	2			YC051-YD157, YL951-YL999		
0228	20	PA		76-3	SPARE	D40102J	28			D40994P	2			YD158-YD170		
0228	20	PA		63-1	SPARE	D40102J	28			D40114P	2			YN231-YN260		
0241	18	PA		2-4	33-22-21	D41064P	A			SM00113		S		YN501-YR328		
0242	18	PA		1-9	33-22-22	D41086P	A			SM00126		S		YN501-YR328		
0243	18	PA		1-2	33-22-31	D41066P	A			SM00114		S		YN501-YR328		
0244	18	PA		8-3	33-22-32	D41084P	A			SM00122		S		YN501		
0244	18	PA		8-9	33-22-32	D41084P	A			SM00122		S		YR301-YR328		
0245	18	PA		1-2	33-22-51	D41066P	B			SM00114		S		YN501-YR328		
0246	18	PA		8-3	33-22-51	D41084P	B			SM00122		S		YN501		
0246	18	PA		8-9	33-22-51	D41084P	B			SM00122		S		YR301-YR328		
0247	18	PA		2-4	33-22-41	D41064P	B			SM00113		S		YN501-YR328		
0248	18	PA		1-9	33-22-41	D41086P	B			SM00126		S		YN501-YR328		

WIRE LIST

D280A108

91-21-11

Section W3150

Page 61

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Fam	FT-IN	Diagram	From				To				
	Wire No.	GA	CO TY					Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3158	286A3158			AB0340A DISCONNECT TO LEFT AFT OVERHEAD (continued)												
0301	20	PA		10-5	33-25-51	SM00108			S		D40762P	1			YC051-YL999	
0301	20	PA		4-5	33-25-51	SM00108			S		D40762P	1			YN231-YN260	
0301	18	PA		10-5	33-25-51	SM00108			S		D40762P	1			YN501	
0301	18	PA		10-6	33-25-51	SM00108			S		D40762P	1			YR301-YR328	
0302	18	PA		10-5	33-25-51	SM00106			S		D40762P	2			YC051-YL999, YN501	
0302	18	PA		4-5	33-25-51	SM00106			S		D40762P	2			YN231-YN260	
0302	18	PA		10-6	33-25-51	SM00106			S		D40762P	2			YR301-YR328	
0303	18	PA		6-6	33-25-51	D40762P		3			GD08054	AC..	1		YC051-YL999, YN501	
0303	18	PA		6-7	33-25-51	D40762P		3			GD08054	AC..	1		YN231-YN260, YR301-YR328	
0401	20	PA		6-9	33-25-51	SM00107			S		D40764P	1			YC051-YL999	
0401	20	PA		5-1	33-25-51	SM00107			S		D40764P	1			YN231-YN260	
0402	18	PA		6-9	33-25-51	SM00109			S		D40764P	2			YC051-YL999	
0402	18	PA		5-1	33-25-51	SM00109			S		D40764P	2			YN231-YN260	
0403	18	PA		2-6	33-25-51	D40764P		3			GD03812	AC..	1		YC051-YN260	
0414	18	PA		9-8	33-22-11	D40102J		14			SM00114		S		YN501-YR328	
0422	18	PA		37-0	33-22-11	D40102J		27			SM00122		S		YN501	
0422	18	PA		47-0	33-22-11	D40102J		27			SM00122		S		YR301-YR328	
0426	18	PA		37-0	33-22-11	D40102J		26			SM00126		S		YN501	
0426	18	PA		47-0	33-22-11	D40102J		26			SM00126		S		YR301-YR328	
0513	18	PA		9-8	33-22-11	D40102J		13			SM00113		S		YN501-YR328	
2401B	18	PB	OL	49-5	33-23-12	D40102J		22			D40106P	12			YC051-YL999	
2401B	18	PB	OL	39-3	33-23-12	D40102J		22			D40106P	12			YN231-YN260	
2401B	18	PB	OL	38-5	33-23-12	D40102J		22			D40109P	12			YN501	
2401B	18	PB	OL	48-6	33-23-12	D40102J		22			D40109P	12			YR301-YR328	
2401R	18	PB	OL	0-0	33-23-12	D40102J		1			D40106P	6			YC051-YN260	
2401R	18	PB	OL	0-0	33-23-12	D40102J		1			D40109P	6			YN501-YR328	
2402B	18	PB	OM	49-5	33-23-12	D40102J		23			D40106P	3			YC051-YL999	
2402B	18	PB	OM	39-3	33-23-12	D40102J		23			D40106P	3			YN231-YN260	
2402B	18	PB	OM	38-5	33-23-12	D40102J		23			D40109P	3			YN501	
2402B	18	PB	OM	48-6	33-23-12	D40102J		23			D40109P	3			YR301-YR328	
2402R	18	PB	OM	0-0	33-23-12	D40102J		2			D40106P	8			YC051-YN260	
2402R	18	PB	OM	0-0	33-23-12	D40102J		2			D40109P	8			YN501-YR328	
2405B	18	PB	OE	49-5	33-23-12	D40102J		24			D40106P	14			YC051-YL999	
2405B	18	PB	OE	48-6	33-23-12	D40102J		24			D40109P	14			YR301-YR328	
2405R	18	PB	OE	0-0	33-23-12	D40102J		5			D40106P	13			YC051-YL999	
2405R	18	PB	OE	0-0	33-23-12	D40102J		5			D40109P	13			YR301-YR328	
2407B	18	PB	OG	11-3	33-23-11	D40102J		17			D40104P	2			YC051-YL999, YR301-YR328	

WIRE LIST

D280A108

91-21-11

Section W3150

Page 62

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3158	286A3158			AB0340A DISCONNECT TO LEFT AFT OVERHEAD (continued)											
2407B	18	PB	OG		11-2	33-23-11	D40102J	17			D40104P	2			YN231-YN501
2407R	18	PB	OG		0-0	33-23-11	D40102J	7			D40104P	1			ALL
2408B	18	PB	OH		11-3	33-23-11	D40102J	18			D40104P	12			YC051-YL999, YR301-YR328
2408B	18	PB	OH		11-2	33-23-11	D40102J	18			D40104P	12			YN231-YN501
2408R	18	PB	OH		0-0	33-23-11	D40102J	8			D40104P	6			ALL
2409B	18	PB	OI		11-3	33-23-11	D40102J	19			D40104P	3			YC051-YL999, YR301-YR328
2409B	18	PB	OI		11-2	33-23-11	D40102J	19			D40104P	3			YN231-YN501
2409R	18	PB	OI		0-0	33-23-11	D40102J	9			D40104P	8			ALL
2410B	18	PB	OJ		11-3	33-23-11	D40102J	20			D40104P	14			YC051-YL999, YR301-YR328
2410B	18	PB	OJ		11-2	33-23-11	D40102J	20			D40104P	14			YN231-YN501
2410R	18	PB	OJ		0-0	33-23-11	D40102J	10			D40104P	13			ALL
2411B	18	PB	OK		49-5	33-23-12	D40102J	21			D40106P	2			YC051-YL999
2411B	18	PB	OK		39-3	33-23-12	D40102J	21			D40106P	2			YN231-YN260
2411B	18	PB	OK		38-5	33-23-12	D40102J	21			D40109P	2			YN501
2411B	18	PB	OK		48-6	33-23-12	D40102J	21			D40109P	2			YR301-YR328
2411R	18	PB	OK		0-0	33-23-12	D40102J	11			D40106P	1			YC051-YN260
2411R	18	PB	OK		0-0	33-23-12	D40102J	11			D40109P	1			YN501-YR328
2415B	18	PB	OP		49-5	33-23-12	D40102J	16			D40106P	15			YC051-YL999
2415B	18	PB	OP		48-6	33-23-12	D40102J	16			D40109P	15			YR301-YR328
2415R	18	PB	OP		0-0	33-23-12	D40102J	15			D40106P	4			YC051-YL999
2415R	18	PB	OP		0-0	33-23-12	D40102J	15			D40109P	4			YR301-YR328
5501	22	CQ			85-1	21-42-11	D40102J	29			D40116P	7			YC051-YL999, YR301-YR328
5501	22	PA			65-8	21-42-11	D40102J	29			D40116P	7			YN231-YN260
5501	22	PA			65-6	21-42-11	D40102J	29			D40116P	7			YN501
5502	22	CQ			85-1	21-42-11	D40102J	30			D40116P	8			YC051-YL999, YR301-YR328
5502	22	PA			65-8	21-42-11	D40102J	30			D40116P	8			YN231-YN260
5502	22	PA			65-6	21-42-11	D40102J	30			D40116P	8			YN501

WIRE LIST

D280A108

91-21-11

Section W3150

Page 63 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To			Effectivity					
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type		Splice	Equip	Term	Type	Splice
I	W3162	286A3162			NS/FSB SIGN-VIDEO PANEL, FORWARD-LEFT											
	3202B	20	PC	YB		4-9	33-25-51	D10337		2		SM00202		S		YD158-YD170
	3202R	20	PC	YB		0-0	33-25-51	D10337		1		SM00102		S		YD158-YD170
	3202Y	20	PC	YB		0-0	33-25-51	D10337		3		SM00302		S		YD158-YD170
	3206B	20	PC	YF		8-7	33-25-51	D10361		2		SM00206		S		YD158-YD170
	3206R	20	PC	YF		0-0	33-25-51	D10361		1		SM00106		S		YD158-YD170
	3206Y	20	PC	YF		0-0	33-25-51	D10361		3		SM00306		S		YD158-YD170
	3212B	20	PC	YL		13-3	33-25-51	D10433		2		SM00516		S		YD158-YD170
	3212R	20	PC	YL		0-0	33-25-51	D10433		1		SM00506		S		YD158-YD170
	3212Y	20	PC	YL		0-0	33-25-51	D10433		3		SM00526		S		YD158-YD170
I	3216B	18	PC	YB		12-0	33-25-51	D41052J		B		SM00612		S		YN501-YR328
I	3216R	18	PC	YB		0-0	33-25-51	D41052J		A		SM00602		S		YN501-YR328
I	3216Y	18	PC	YB		0-0	33-25-51	D41052J		C		SM00622		S		YN501-YR328
	3218B	18	PC	YF		24-9	33-25-51	D41054J		B		SM00612		S		YN501
I	3218B	18	PC	YF		34-8	33-25-51	D41054J		B		SM00612		S		YR301-YR328
I	3218R	18	PC	YF		0-0	33-25-51	D41054J		A		SM00602		S		YN501-YR328
I	3218Y	18	PC	YF		0-0	33-25-51	D41054J		C		SM00622		S		YN501-YR328
I	3401B	20	PC	A2		6-8	33-25-51	SM00002			S	D10349		2		YC051-YD157
I	3401R	20	PC	A2		0-0	33-25-51	SM00001			S	D10349		1		YC051-YD157
I	3401Y	20	PC	A2		0-0	33-25-51	SM00003			S	D10349		3		YC051-YD157
I	3402B	20	PC	B2		4-7	33-25-51	SM00012			S	D10361		2		YC051-YD157
I	3402R	20	PC	B2		0-0	33-25-51	SM00011			S	D10361		1		YC051-YD157
I	3402Y	20	PC	B2		0-0	33-25-51	SM00013			S	D10361		3		YC051-YD157
I	3403B	20	PC	C2		4-2	33-25-51	SM00022			S	D10385		2		YC051-YD157
I	3403R	20	PC	C2		0-0	33-25-51	SM00021			S	D10385		1		YC051-YD157
I	3403Y	20	PC	C2		0-0	33-25-51	SM00023			S	D10385		3		YC051-YD157
I	3404B	20	PC	D2		4-2	33-25-51	SM00032			S	D10397		2		YC051-YD157
I	3404R	20	PC	D2		0-0	33-25-51	SM00031			S	D10397		1		YC051-YD157
I	3404Y	20	PC	D2		0-0	33-25-51	SM00033			S	D10397		3		YC051-YD157
I	3405B	20	PC	E2		12-6	33-25-51	SM00032			S	D10421		2		YC051-YD157
I	3405R	20	PC	E2		0-0	33-25-51	SM00031			S	D10421		1		YC051-YD157
I	3405Y	20	PC	E2		0-0	33-25-51	SM00033			S	D10421		3		YC051-YD157
I	3431B	20	PC	F3		2-4	33-25-51	D40762J		2		SM00002		S		YC051-YD157
I	3431R	20	PC	F3		0-0	33-25-51	D40762J		1		SM00001		S		YC051-YD157
I	3431Y	20	PC	F3		0-0	33-25-51	D40762J		3		SM00003		S		YC051-YD157
I	3432B	20	PC	G3		7-10	33-25-51	SM00002			S	SM00012		S		YC051-YD157
I	3432R	20	PC	G3		0-0	33-25-51	SM00001			S	SM00011		S		YC051-YD157
I	3432Y	20	PC	G3		0-0	33-25-51	SM00003			S	SM00013		S		YC051-YD157
I	3433B	20	PC	H3		8-6	33-25-51	SM00012			S	SM00022		S		YC051-YD157
I	3433R	20	PC	H3		0-0	33-25-51	SM00011			S	SM00021		S		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W3160

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3162	286A3162			NS/FSB SIGN-VIDEO PANEL, FORWARD-LEFT (continued)											
3433Y	20	PC	H3		0-0	33-25-51	SM00013		S		SM00023		S		YC051-YD157
3434B	20	PC	I3		8-5	33-25-51	SM00022		S		SM00032		S		YC051-YD157
3434R	20	PC	I3		0-0	33-25-51	SM00021		S		SM00031		S		YC051-YD157
3434Y	20	PC	I3		0-0	33-25-51	SM00023		S		SM00033		S		YC051-YD157
3502B	20	PC	B8		8-3	33-25-51	SM00206		S		SM00512		S		YD158-YD170
3502R	20	PC	B8		0-0	33-25-51	SM00106		S		SM00502		S		YD158-YD170
3502Y	20	PC	B8		0-0	33-25-51	SM00306		S		SM00522		S		YD158-YD170
3506B	20	PC	F8		8-5	33-25-51	SM00512		S		SM00516		S		YD158-YD170
3506R	20	PC	F8		0-0	33-25-51	SM00502		S		SM00506		S		YD158-YD170
3506Y	20	PC	F8		0-0	33-25-51	SM00522		S		SM00526		S		YD158-YD170
3512B	20	PC	L8		8-0	33-25-51	D10385		2		SM00512		S		YD158-YD170
3512R	20	PC	L8		0-0	33-25-51	D10385		1		SM00502		S		YD158-YD170
3512Y	20	PC	L8		0-0	33-25-51	D10385		3		SM00522		S		YD158-YD170
3516B	20	PC	P8		4-7	33-25-51	D10409		2		SM00516		S		YD158-YD170
3516R	20	PC	P8		0-0	33-25-51	D10409		1		SM00506		S		YD158-YD170
3516Y	20	PC	P8		0-0	33-25-51	D10409		3		SM00526		S		YD158-YD170
3602B	20	PC	B4		2-2	33-25-51	D40762J		2		SM00202		S		YD158-YD170
3602B	18	PC	B4		10-2	33-25-51	D40762J		2		SM00612		S		YN501
3602B	18	PC	B4		10-7	33-25-51	D40762J		2		SM00612		S		YR301-YR328
3602R	20	PC	B4		0-0	33-25-51	D40762J		1		SM00102		S		YD158-YD170
3602R	18	PC	B4		0-0	33-25-51	D40762J		1		SM00602		S		YN501-YR328
3602Y	20	PC	B4		0-0	33-25-51	D40762J		3		SM00302		S		YD158-YD170
3602Y	18	PC	B4		0-0	33-25-51	D40762J		3		SM00622		S		YN501-YR328
3606B	20	PC	F4		6-11	33-25-51	SM00202		S		SM00206		S		YD158-YD170
3606R	20	PC	F4		0-0	33-25-51	SM00102		S		SM00106		S		YD158-YD170
3606Y	20	PC	F4		0-0	33-25-51	SM00302		S		SM00306		S		YD158-YD170
W3164	286A3164			NS/FSB SIGN-VIDEO PANEL, AFT-LEFT											
3206B	20	PC	YF		8-6	33-25-51	D10457		2		SM00206		S		YD158-YD170
3206R	20	PC	YF		0-0	33-25-51	D10457		1		SM00106		S		YD158-YD170
3206Y	20	PC	YF		0-0	33-25-51	D10457		3		SM00306		S		YD158-YD170
3210B	20	PC	YJ		5-3	33-25-51	D10481		2		SM00210		S		YD158-YD170
3210R	20	PC	YJ		0-0	33-25-51	D10481		1		SM00110		S		YD158-YD170
3210Y	20	PC	YJ		0-0	33-25-51	D10481		3		SM00310		S		YD158-YD170
3212B	20	PC	YL		7-0	33-25-51	D10517		2		SM00212		S		YD158-YD170
3212R	20	PC	YL		0-0	33-25-51	D10517		1		SM00112		S		YD158-YD170
3212Y	20	PC	YL		0-0	33-25-51	D10517		3		SM00312		S		YD158-YD170
3214B	20	PC	YN		11-2	33-25-51	D10977		2		SM00212		S		YD158-YD170
3214R	20	PC	YN		0-0	33-25-51	D10977		1		SM00112		S		YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W3160

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3164		286A3164			NS/FSB SIGN-VIDEO PANEL, AFT-LEFT (continued)											
3214Y		20		PC	YN	0-0	33-25-51	D10977		3		SM00312		S		YD158-YD170
3401B		20		PC	A2	7-8	33-25-51	SM00002		S		D10433	2			YC051-YD157
3401R		20		PC	A2	0-0	33-25-51	SM00001		S		D10433	1			YC051-YD157
3401Y		20		PC	A2	0-0	33-25-51	SM00003		S		D10433	3			YC051-YD157
3402B		20		PC	B2	4-9	33-25-51	SM00012		S		D10457	2			YC051-YD157
3402R		20		PC	B2	0-0	33-25-51	SM00011		S		D10457	1			YC051-YD157
3402Y		20		PC	B2	0-0	33-25-51	SM00013		S		D10457	3			YC051-YD157
3403B		20		PC	C2	4-11	33-25-51	SM00022		S		D10469	2			YC051-YD157
3403R		20		PC	C2	0-0	33-25-51	SM00021		S		D10469	1			YC051-YD157
3403Y		20		PC	C2	0-0	33-25-51	SM00023		S		D10469	3			YC051-YD157
3404B		20		PC	D2	4-5	33-25-51	SM00032		S		D10493	2			YC051-YD157
3404R		20		PC	D2	0-0	33-25-51	SM00031		S		D10493	1			YC051-YD157
3404Y		20		PC	D2	0-0	33-25-51	SM00033		S		D10493	3			YC051-YD157
3405B		20		PC	E2	4-9	33-25-51	SM00042		S		D10505	2			YC051-YD157
3405R		20		PC	E2	0-0	33-25-51	SM00041		S		D10505	1			YC051-YD157
3405Y		20		PC	E2	0-0	33-25-51	SM00043		S		D10505	3			YC051-YD157
3406B		20		PC	F2	12-0	33-25-51	SM00042		S		D10517	2			YC051-YD157
3406R		20		PC	F2	0-0	33-25-51	SM00041		S		D10517	1			YC051-YD157
3406Y		20		PC	F2	0-0	33-25-51	SM00043		S		D10517	3			YC051-YD157
3431B		20		PC	F3	2-0	33-25-51	D40764J		2		SM00002		S		YC051-YD157
3431R		20		PC	F3	0-0	33-25-51	D40764J		1		SM00001		S		YC051-YD157
3431Y		20		PC	F3	0-0	33-25-51	D40764J		3		SM00003		S		YC051-YD157
3432B		20		PC	G3	6-3	33-25-51	SM00002		S		SM00012		S		YC051-YD157
3432R		20		PC	G3	0-0	33-25-51	SM00001		S		SM00011		S		YC051-YD157
3432Y		20		PC	G3	0-0	33-25-51	SM00003		S		SM00013		S		YC051-YD157
3433B		20		PC	H3	8-1	33-25-51	SM00012		S		SM00022		S		YC051-YD157
3433R		20		PC	H3	0-0	33-25-51	SM00011		S		SM00021		S		YC051-YD157
3433Y		20		PC	H3	0-0	33-25-51	SM00013		S		SM00023		S		YC051-YD157
3434B		20		PC	I3	8-6	33-25-51	SM00022		S		SM00032		S		YC051-YD157
3434R		20		PC	I3	0-0	33-25-51	SM00021		S		SM00031		S		YC051-YD157
3434Y		20		PC	I3	0-0	33-25-51	SM00023		S		SM00033		S		YC051-YD157
3435B		20		PC	J3	7-9	33-25-51	SM00032		S		SM00042		S		YC051-YD157
3435R		20		PC	J3	0-0	33-25-51	SM00031		S		SM00041		S		YC051-YD157
3435Y		20		PC	J3	0-0	33-25-51	SM00033		S		SM00043		S		YC051-YD157
3606B		20		PC	F4	2-1	33-25-51	D40764J		2		SM00206		S		YD158-YD170
3606R		20		PC	F4	0-0	33-25-51	D40764J		1		SM00106		S		YD158-YD170
3606Y		20		PC	F4	0-0	33-25-51	D40764J		3		SM00306		S		YD158-YD170
3610B		20		PC	J4	6-9	33-25-51	SM00206		S		SM00210		S		YD158-YD170
3610R		20		PC	J4	0-0	33-25-51	SM00106		S		SM00110		S		YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W3160

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3164	286A3164				NS/FSB SIGN-VIDEO PANEL, AFT-LEFT (continued)										
3610Y	20	PC	J4		0-0	33-25-51	SM00306		S		SM00310		S		YD158-YD170
3612B	20	PC	L4		10-10	33-25-51	SM00212		S		SM00712		S		YD158-YD170
3612R	20	PC	L4		0-0	33-25-51	SM00112		S		SM00702		S		YD158-YD170
3612Y	20	PC	L4		0-0	33-25-51	SM00312		S		SM00722		S		YD158-YD170
3702B	20	PC	B8		4-11	33-25-51	SM00210		S		SM00712		S		YD158-YD170
3702R	20	PC	B8		0-0	33-25-51	SM00110		S		SM00702		S		YD158-YD170
3702Y	20	PC	B8		0-0	33-25-51	SM00310		S		SM00722		S		YD158-YD170
3712B	20	PC	L8		6-2	33-25-51	D10493	2			SM00712		S		YD158-YD170
3712R	20	PC	L8		0-0	33-25-51	D10493	1			SM00702		S		YD158-YD170
3712Y	20	PC	L8		0-0	33-25-51	D10493	3			SM00722		S		YD158-YD170
W3166	286A3166				LED LIGHTING - CEILING/WASH LEFT										
0001	18	PA			3-7	33-22-41	D14446		B		SM00001		S		YN501
0002	18	PA			6-6	33-22-41	D14446		C		GD03860	AC..	1		YN501
0003	18	PA			6-6	33-22-41	D14446		A		GD03860	ST..	1		YN501
0011	18	PA			3-7	33-22-41	D14454		B		SM00001		S		YN501
0012	18	PA			6-6	33-22-41	D14454		C		GD03870	AC..	1		YN501
0013	18	PA			6-6	33-22-41	D14454		A		GD03870	ST..	1		YN501
0014	18	PA			4-8	33-22-41	D41064J		B		SM00001		S		YN501
0014	18	PA			3-11	33-22-41	D41064J		B		SM00017		S		YR301-YR328
0015	18	PA			9-10	33-22-41	SM00001		S		SM00002		S		YN501
0016	18	PA			11-11	33-22-41	SM00002		S		SM00003		S		YN501
0017	18	PA			22-3	33-22-41	D41086J		B		SM00004		S		YN501
0017	18	PA			6-2	33-22-41	D41086J		B		SM00008		S		YR301-YR328
0018	18	PA			14-0	33-22-41	SM00018		S		SM00006		S		YR301-YR328
0019	18	PA			11-3	33-22-41	SM00006		S		SM00007		S		YR301-YR328
0020	18	PA			11-0	33-22-41	SM00008		S		SM00009		S		YR301-YR328
0021	18	PA			10-4	33-22-41	SM00009		S		SM00010		S		YR301-YR328
0022	18	PA			2-10	33-22-41	SM00018		S		SM00017		S		YR301-YR328
0024	18	PA			7-4	33-22-41	D14960		B		SM00018		S		YR301-YR328
0025	18	PA			6-6	33-22-41	D14960		C		GD08010	AC..	1		YR301-YR328
0026	18	PA			6-6	33-22-41	D14960		A		GD08010	ST..	1		YR301-YR328
0034	18	PA			4-5	33-22-41	D14962		B		SM00006		S		YR301-YR328
0035	18	PA			6-6	33-22-41	D14962		C		GD08012	AC..	1		YR301-YR328
0036	18	PA			6-6	33-22-41	D14962		A		GD08012	ST..	1		YR301-YR328
0044	18	PA			4-2	33-22-41	D14964		B		SM00006		S		YR301-YR328
0045	18	PA			6-6	33-22-41	D14964		C		GD08012	AC..	1		YR301-YR328
0046	18	PA			6-6	33-22-41	D14964		A		GD08012	ST..	1		YR301-YR328
0054	18	PA			4-10	33-22-41	D14966		B		SM00007		S		YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3160

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3166		286A3166			LED LIGHTING - CEILING/WASH LEFT (continued)											
0055		18		PA		6-6	33-22-41	D14966		C		GD03742	AC..	1		YR301-YR328
0056		18		PA		6-6	33-22-41	D14966		A		GD03742	ST..	1		YR301-YR328
0061		18		PA		3-10	33-22-41	D14458		B		SM00002		S		YN501
0062		18		PA		6-6	33-22-41	D14458		C		GD03844	AC..	1		YN501
0063		18		PA		6-6	33-22-41	D14458		A		GD03844	ST..	1		YN501
0071		18		PA		4-11	33-22-41	D14462		B		SM00002		S		YN501
0072		18		PA		6-6	33-22-41	D14462		C		GD03742	AC..	1		YN501
0073		18		PA		6-6	33-22-41	D14462		A		GD03742	ST..	1		YN501
0081		18		PA		4-2	33-22-41	D14466		B		SM00003		S		YN501
0082		18		PA		6-6	33-22-41	D14466		C		GD03728	AC..	1		YN501
0083		18		PA		6-6	33-22-41	D14466		A		GD03728	ST..	1		YN501
0084		18		PA		2-4	33-22-41	D14464		B		SM00018		S		YR301-YR328
0085		18		PA		6-6	33-22-41	D14464		C		GD03866	AC..	1		YR301-YR328
0086		18		PA		6-6	33-22-41	D14464		A		GD03866	ST..	1		YR301-YR328
0101		18		PA		4-4	33-22-41	D15368		B		SM00003		S		YN501
0102		18		PA		6-6	33-22-41	D15368		C		GD04004	AC..	1		YN501
0103		18		PA		6-6	33-22-41	D15368		A		GD04004	ST..	1		YN501
0104		18		PA		4-3	33-22-41	D14968		B		SM00007		S		YR301-YR328
0105		18		PA		6-6	33-22-41	D14968		C		GD03728	AC..	1		YR301-YR328
0106		18		PA		6-6	33-22-41	D14968		A		GD03728	ST..	1		YR301-YR328
0111		18		PA		16-8	33-22-41	D15350		B		SM00004		S		YN501
0112		18		PA		6-6	33-22-41	D15350		C		GD03848	AC..	1		YN501
0113		18		PA		6-6	33-22-41	D15350		A		GD03848	ST..	1		YN501
0114		18		PA		5-1	33-22-41	D15394		B		SM00008		S		YR315-YR316, YR319
0115		18		PA		6-6	33-22-41	D15394		C		GD04004	AC..	1		YR315-YR316, YR319
0116		18		PA		6-6	33-22-41	D15394		A		GD04004	ST..	1		YR315-YR316, YR319
0121		18		PA		11-6	33-22-41	D15352		B		SM00004		S		YN501
0122		18		PA		6-6	33-22-41	D15352		C		GD03756	AC..	1		YN501
0123		18		PA		6-6	33-22-41	D15352		A		GD03756	ST..	1		YN501
0131		18		PA		6-4	33-22-41	D15354		B		SM00004		S		YN501
0132		18		PA		6-6	33-22-41	D15354		C		GD03850	AC..	1		YN501
0133		18		PA		6-6	33-22-41	D15354		A		GD03850	ST..	1		YN501
0134		18		PA		4-8	33-22-41	D14978		B		SM00009		S		YR301-YR314, YR317-YR318, YR320-YR328
0135		18		PA		6-6	33-22-41	D14978		C		GD03756	AC..	1		YR301-YR314, YR317-YR318, YR320-YR328

WIRE LIST

D280A108

91-21-11

Section W3160

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3166	286A3166				LED LIGHTING - CEILING/WASH LEFT (continued)										
0136	18		PA		6-6	33-22-41	D14978		A		GD03756	ST..	1		YR301-YR314, YR317-YR318, YR320-YR328
0144	18		PA		3-2	33-22-41	D14980		B		SM00009		S		YR301-YR328
0145	18		PA		6-6	33-22-41	D14980		C		GD08020	AC..	1		YR301-YR328
0146	18		PA		6-6	33-22-41	D14980		A		GD08020	ST..	1		YR301-YR328
0154	18		PA		4-9	33-22-41	D14982		B		SM00010		S		YR301-YR328
0155	18		PA		6-6	33-22-41	D14982		C		GD08028	AC..	1		YR301-YR328
0156	18		PA		6-6	33-22-41	D14982		A		GD08028	ST..	1		YR301-YR328
0164	18		PA		4-5	33-22-41	D15400		B		SM00010		S		YR301-YR328
0165	18		PA		6-6	33-22-41	D15400		C		GD03764	AC..	1		YR301-YR328
0166	18		PA		6-6	33-22-41	D15400		A		GD03764	ST..	1		YR301-YR328
0201	18		PA		3-7	33-22-21	D14750		B		SM00011		S		YN501
0202	18		PA		6-6	33-22-21	D14750		C		GD03860	AC..	1		YN501
0203	18		PA		6-6	33-22-21	D14750		A		GD03860	ST..	1		YN501
0204	18		PA		1-4	33-22-21	D41064J		A		SM00011		S		YN501
0204	18		PA		3-11	33-22-21	D41064J		A		SM00011		S		YR301-YR328
0205	18		PA		3-10	33-22-21	SM00012			S	SM00011		S		YN501
0205	18		PA		6-6	33-22-21	SM00011			S	SM00015		S		YR301-YR328
0206	18		PA		9-10	33-22-21	SM00013			S	SM00012		S		YN501
0206	18		PA		10-10	33-22-21	SM00015			S	SM00016		S		YR301-YR328
0207	18		PA		11-11	33-22-21	SM00014			S	SM00013		S		YN501
0207	18		PA		11-3	33-22-21	SM00014			S	SM00016		S		YR301-YR328
0211	18		PA		3-7	33-22-21	D14442		B		SM00012		S		YN501
0212	18		PA		6-6	33-22-21	D14442		C		GD03870	AC..	1		YN501
0213	18		PA		6-6	33-22-21	D14442		A		GD03870	ST..	1		YN501
0221	18		PA		3-10	33-22-21	D14438		B		SM00013		S		YN501
0222	18		PA		6-6	33-22-21	D14438		C		GD03844	AC..	1		YN501
0223	18		PA		6-6	33-22-21	D14438		A		GD03844	ST..	1		YN501
0224	18		PA		6-6	33-22-21	D14898		B		SM00011		S		YR301-YR328
0225	18		PA		6-6	33-22-21	D14898		C		GD03860	AC..	1		YR301-YR328
0226	18		PA		6-6	33-22-21	D14898		A		GD03860	ST..	1		YR301-YR328
0254	18		PA		4-5	33-22-21	D14884		B		SM00016		S		YR301-YR328
0255	18		PA		6-6	33-22-21	D14884		C		GD08012	AC..	1		YR301-YR328
0256	18		PA		6-6	33-22-21	D14884		A		GD08012	ST..	1		YR301-YR328
0264	18		PA		4-2	33-22-21	D14882		B		SM00016		S		YR301-YR328
0265	18		PA		6-6	33-22-21	D14882		C		GD08012	AC..	1		YR301-YR328
0266	18		PA		6-6	33-22-21	D14882		A		GD08012	ST..	1		YR301-YR328
0271	18		PA		4-11	33-22-21	D14434		B		SM00013		S		YN501

WIRE LIST

D280A108

91-21-11

Section W3160

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3166		286A3166			LED LIGHTING - CEILING/WASH LEFT (continued)											
0272		18		PA		6-6	33-22-21	D14434		C		GD03742	AC..	1		YN501
0273		18		PA		6-6	33-22-21	D14434		A		GD03742	ST..	1		YN501
0274		18		PA		4-10	33-22-21	D14880		B		SM00014		S		YR301-YR328
0275		18		PA		6-6	33-22-21	D14880		C		GD03742	AC..	1		YR301-YR328
0276		18		PA		6-6	33-22-21	D14880		A		GD03742	ST..	1		YR301-YR328
0281		18		PA		4-2	33-22-21	D14430		B		SM00014		S		YN501
0282		18		PA		6-6	33-22-21	D14430		C		GD03728	AC..	1		YN501
0283		18		PA		6-6	33-22-21	D14430		A		GD03728	ST..	1		YN501
0284		18		PA		4-3	33-22-21	D14878		B		SM00014		S		YR301-YR328
0285		18		PA		6-6	33-22-21	D14878		C		GD03728	AC..	1		YR301-YR328
0286		18		PA		6-6	33-22-21	D14878		A		GD03728	ST..	1		YR301-YR328
0291		18		PA		4-4	33-22-21	D14408		B		SM00014		S		YN501
0292		18		PA		6-6	33-22-21	D14408		C		GD04004	AC..	1		YN501
0293		18		PA		4-10	33-22-21	D14408		A		GD04004	ST..	1		YN501
0294		18		PA		9-11	33-22-21	D14876		B		SM00014		S		YR301-YR328
0295		18		PA		6-6	33-22-21	D14876		C		GD04004	AC..	1		YR301-YR328
0296		18		PA		6-6	33-22-21	D14876		A		GD04004	ST..	1		YR301-YR328
0304		18		PA		10-11	33-22-22	D41086J		A		SM00022		S		YN501
0304		18		PA		6-2	33-22-22	D41086J		A		SM00021		S		YR301-YR328
0305		18		PA		11-0	33-22-22	SM00021		S		SM00024		S		YR301-YR328
0307		18		PA		10-4	33-22-22	SM00024		S		SM00025		S		YR301-YR328
0308		18		PA		5-1	33-22-22	SM00025		S		SM00026		S		YR301-YR328
0309		18		PA		12-4	33-22-22	SM00022		S		SM00027		S		YN501
0331		18		PA		4-10	33-22-22	D15332		B		SM00022		S		YN501
0332		18		PA		6-6	33-22-22	D15332		C		GD03848	AC..	1		YN501
0333		18		PA		6-6	33-22-22	D15332		A		GD03848	ST..	1		YN501
0334		18		PA		5-0	33-22-22	D14868		B		SM00021		S		YR315-YR316, YR319
0335		18		PA		6-6	33-22-22	D14868		C		GD03848	AC..	1		YR315-YR316, YR319
0336		18		PA		6-6	33-22-22	D14868		A		GD03848	ST..	1		YR315-YR316, YR319
0341		18		PA		3-10	33-22-22	D15330		B		SM00022		S		YN501
0342		18		PA		6-6	33-22-22	D15330		C		GD03756	AC..	1		YN501
0343		18		PA		6-6	33-22-22	D15330		A		GD03756	ST..	1		YN501
0351		18		PA		6-4	33-22-22	D15328		B		SM00027		S		YN501
0352		18		PA		6-6	33-22-22	D15328		C		GD03850	AC..	1		YN501
0353		18		PA		6-6	33-22-22	D15328		A		GD03850	ST..	1		YN501
0354		18		PA		3-2	33-22-22	D14860		B		SM00024		S		YR301-YR314, YR317-YR318, YR320-YR328

WIRE LIST

D280A108

91-21-11

Section W3160

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3166	286A3166			LED LIGHTING - CEILING/WASH LEFT (continued)											
0355	18	PA			6-6	33-22-22	D14860		C		GD08020	AC..	1		YR301-YR314, YR317-YR318, YR320-YR328
0356	18	PA			6-6	33-22-22	D14860		A		GD08020	ST..	1		YR301-YR314, YR317-YR318, YR320-YR328
0361	18	PA			1-6	33-22-22	D15326		B		SM00027		S		YN501
0362	18	PA			6-6	33-22-22	D15326		C		GD03990	AC..	1		YN501
0363	18	PA			6-6	33-22-22	D15326		A		GD03990	ST..	1		YN501
0364	18	PA			4-9	33-22-22	D14858		B		SM00025		S		YR301-YR328
0365	18	PA			6-6	33-22-22	D14858		C		GD08028	AC..	1		YR301-YR328
0366	18	PA			6-6	33-22-22	D14858		A		GD08028	ST..	1		YR301-YR328
0374	18	PA			4-5	33-22-22	D14856		B		SM00025		S		YR301-YR328
0375	18	PA			6-6	33-22-22	D14856		C		GD03764	AC..	1		YR301-YR328
0376	18	PA			6-6	33-22-22	D14856		A		GD03764	ST..	1		YR301-YR328
0384	18	PA			3-0	33-22-22	D15372		B		SM00026		S		YR301-YR328
0385	18	PA			6-6	33-22-22	D15372		C		GD03990	AC..	1		YR301-YR328
0386	18	PA			6-6	33-22-22	D15372		A		GD03990	ST..	1		YR301-YR328
0394	18	PA			4-3	33-22-22	D14848		B		SM00026		S		YR301-YR328
0395	18	PA			6-6	33-22-22	D14848		C		GD03990	AC..	1		YR301-YR328
0396	18	PA			6-6	33-22-22	D14848		A		GD03990	ST..	1		YR301-YR328
0404	18	PA			3-8	33-22-21	D14810		B		SM00015		S		YR301-YR328
0405	18	PA			6-6	33-22-21	D14810		C		GD08010	AC..	1		YR301-YR328
0406	18	PA			6-6	33-22-21	D14810		A		GD08010	ST..	1		YR301-YR328
0421	18	PA			2-10	33-22-22	D15320		B		SM00027		S		YN501
0422	18	PA			6-6	33-22-22	D15320		C		GD03990	AC..	1		YN501
0423	18	PA			6-6	33-22-22	D15320		A		GD03990	ST..	1		YN501
0524	18	PA			5-3	33-22-22	D14806		B		SM00024		S		YR315-YR316, YR319
0525	18	PA			6-6	33-22-22	D14806		C		GD03756	AC..	1		YR315-YR316, YR319
0526	18	PA			6-6	33-22-22	D14806		A		GD03756	ST..	1		YR315-YR316, YR319
0534	18	PA			4-8	33-22-21	D15378		B		SM00011		S		YR301-YR328
0535	18	PA			6-6	33-22-21	D15378		C		GD03866	AC..	1		YR301-YR328
0536	18	PA			6-6	33-22-21	D15378		A		GD03866	ST..	1		YR301-YR328
0544	18	PA			3-2	33-22-22	D15374		B		SM00024		S		YR315-YR316, YR319
0545	18	PA			6-6	33-22-22	D15374		C		GD08020	AC..	1		YR315-YR316, YR319
0546	18	PA			6-6	33-22-22	D15374		A		GD08020	ST..	1		YR315-YR316, YR319
0554	18	PA			3-10	33-22-41	D15398		B		SM00009		S		YR315-YR316, YR319
0555	18	PA			6-6	33-22-41	D15398		C		GD03756	AC..	1		YR315-YR316, YR319
0556	18	PA			6-6	33-22-41	D15398		A		GD03756	ST..	1		YR315-YR316, YR319

WIRE LIST

D280A108

91-21-11

Section W3160

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3166	286A3166			LED LIGHTING - CEILING/WASH LEFT (continued)											
0564	18		PA		2-11	33-22-41	D15392		B		SM00017		S		YR301-YR328
0565	18		PA		6-6	33-22-41	D15392		C		GD03860	AC..	1		YR301-YR328
0566	18		PA		6-6	33-22-41	D15392		A		GD03860	ST..	1		YR301-YR328
0574	18		PA		4-8	33-22-22	D15284		B		SM00024		S		YR301-YR314, YR317-YR318, YR320-YR328
0575	18		PA		6-6	33-22-22	D15284		C		GD03756	AC..	1		YR301-YR314, YR317-YR318, YR320-YR328
0576	18		PA		6-6	33-22-22	D15284		A		GD03756	ST..	1		YR301-YR314, YR317-YR318, YR320-YR328
0584	18		PA		3-6	33-22-22	D15286		B		SM00021		S		YR301-YR314, YR317-YR318, YR320-YR328
0585	18		PA		6-6	33-22-22	D15286		C		GD03848	AC..	1		YR301-YR314, YR317-YR318, YR320-YR328
0586	18		PA		6-6	33-22-22	D15286		A		GD03848	ST..	1		YR301-YR314, YR317-YR318, YR320-YR328
0604	18		PA		5-1	33-22-41	D15300		B		SM00008		S		YR301-YR314, YR317-YR318, YR320-YR328
0605	18		PA		6-6	33-22-41	D15300		C		GD04004	AC..	1		YR301-YR314, YR317-YR318, YR320-YR328
0606	18		PA		6-6	33-22-41	D15300		A		GD04004	ST..	1		YR301-YR314, YR317-YR318, YR320-YR328
0614	18		PA		3-6	33-22-41	D15302		B		SM00008		S		YR301-YR314, YR317-YR318, YR320-YR328
0615	18		PA		6-6	33-22-41	D15302		C		GD03848	AC..	1		YR301-YR314, YR317-YR318, YR320-YR328
0616	18		PA		6-6	33-22-41	D15302		A		GD03848	ST..	1		YR301-YR314, YR317-YR318, YR320-YR328

WIRE LIST

D280A108

91-21-11

Section W3160

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3166	286A3166				LED LIGHTING - CEILING/WASH LEFT (continued)											
2001B	24		OT	EA	2-9	33-22-41		D41076J		2		D14452		2		YN501
2001B	24		OT	EA	3-0	33-22-41		D41076J		2		D15390		2		YR301-YR328
2001W	24		OT	EA	0-0	33-22-41		D41076J		1		D14452		1		YN501
2001W	24		OT	EA	0-0	33-22-41		D41076J		1		D15390		1		YR301-YR328
2001Z				EA	0-0	33-22-41		D41076J		5		D14452		5		YN501
2001Z				EA	0-0	33-22-41		D41076J		5		D15390		5		YR301-YR328
2002B	24		PL	EB	2-9	33-22-41		D41076J		4		D14452		4		YN501
2002B	24		PL	EB	3-0	33-22-41		D41076J		4		D15390		4		YR301-YR328
2002R	24		PL	EB	0-0	33-22-41		D41076J		3		D14452		3		YN501
2002R	24		PL	EB	0-0	33-22-41		D41076J		3		D15390		3		YR301-YR328
2005B	24		OT	EE	6-1	33-22-21		D14436		2		D14440		2		YN501
2005W	24		OT	EE	0-0	33-22-21		D14436		1		D14440		1		YN501
2005Z				EE	0-0	33-22-21		D14436		5		D14440		5		YN501
2006B	24		PL	EF	6-1	33-22-21		D14436		4		D14440		4		YN501
2006R	24		PL	EF	0-0	33-22-21		D14436		3		D14440		3		YN501
2017B	24		OT	ER	10-7	33-22-22		D14870		2		D15376		2		YR315-YR316, YR319
2017W	24		OT	ER	0-0	33-22-22		D14870		1		D15376		1		YR315-YR316, YR319
2017Z				ER	0-0	33-22-22		D14870		5		D15376		5		YR315-YR316, YR319
2018B	24		PL	ES	10-7	33-22-22		D14870		4		D15376		4		YR315-YR316, YR319
2018R	24		PL	ES	0-0	33-22-22		D14870		3		D15376		3		YR315-YR316, YR319
2021B	24		OT	EV	4-6	33-22-22		D14850		2		D15370		2		YR301-YR328
2021W	24		OT	EV	0-0	33-22-22		D14850		1		D15370		1		YR301-YR328
2021Z				EV	0-0	33-22-22		D14850		5		D15370		5		YR301-YR328
2022B	24		PL	EW	4-6	33-22-22		D14850		4		D15370		4		YR301-YR328
2022R	24		PL	EW	0-0	33-22-22		D14850		3		D15370		3		YR301-YR328
2023B	24		OT	EX	4-5	33-22-22		D14844		2		D14846		2		YR301-YR328
2023W	24		OT	EX	0-0	33-22-22		D14844		1		D14846		1		YR301-YR328
2023Z				EX	0-0	33-22-22		D14844		5		D14846		5		YR301-YR328
2024B	24		PL	EY	4-5	33-22-22		D14844		4		D14846		4		YR301-YR328
2024R	24		PL	EY	0-0	33-22-22		D14844		3		D14846		3		YR301-YR328
2047B	24		OT	HW	4-10	33-22-22		D15258		2		D14804		2		YR315-YR316, YR319
2047W	24		OT	HW	0-0	33-22-22		D15258		1		D14804		1		YR315-YR316, YR319
2047Z				HW	0-0	33-22-22		D15258		5		D14804		5		YR315-YR316, YR319
2048B	24		PL	HX	4-10	33-22-22		D15258		4		D14804		4		YR315-YR316, YR319
2048R	24		PL	HX	0-0	33-22-22		D15258		3		D14804		3		YR315-YR316, YR319
2049B	24		OT	HY	10-4	33-22-22		D14808		2		D14866		2		YR315-YR316, YR319
2049W	24		OT	HY	0-0	33-22-22		D14808		1		D14866		1		YR315-YR316, YR319
2049Z				HY	0-0	33-22-22		D14808		5		D14866		5		YR315-YR316, YR319
2050B	24		PL	HZ	10-4	33-22-22		D14808		4		D14866		4		YR315-YR316, YR319

WIRE LIST

D280A108

91-21-11

Section W3160

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3166	286A3166			LED LIGHTING - CEILING/WASH LEFT (continued)											
2050R	24	PL	HZ	0-0	33-22-22	D14808		3			D14866	3			YR315-YR316, YR319
2051B	24	OT	IA	15-2	33-22-41	D15416		2			D15396	2			YR315-YR316, YR319
2051W	24	OT	IA	0-0	33-22-41	D15416		1			D15396	1			YR315-YR316, YR319
2051Z			IA	0-0	33-22-41	D15416		5			D15396	5			YR315-YR316, YR319
2052B	24	PL	IB	15-2	33-22-41	D15416		4			D15396	4			YR315-YR316, YR319
2052R	24	PL	IB	0-0	33-22-41	D15416		3			D15396	3			YR315-YR316, YR319
2053B	24	OT	IC	5-0	33-22-21	D14896		2			D14798	2			YR301-YR328
2053W	24	OT	IC	0-0	33-22-21	D14896		1			D14798	1			YR301-YR328
2053Z			IC	0-0	33-22-21	D14896		5			D14798	5			YR301-YR328
2054B	24	PL	ID	5-0	33-22-21	D14896		4			D14798	4			YR301-YR328
2054R	24	PL	ID	0-0	33-22-21	D14896		3			D14798	3			YR301-YR328
2055B	24	OT	GE	4-9	33-22-22	D15322		2			D15324	2			YN501
2055W	24	OT	GE	0-0	33-22-22	D15322		1			D15324	1			YN501
2055Z			GE	0-0	33-22-22	D15322		5			D15324	5			YN501
2056B	24	PL	GF	4-9	33-22-22	D15322		4			D15324	4			YN501
2056R	24	PL	GF	0-0	33-22-22	D15322		3			D15324	3			YN501
2057B	24	OT	GG	4-9	33-22-22	D15318		2			D15366	2			YN501
2057W	24	OT	GG	0-0	33-22-22	D15318		1			D15366	1			YN501
2057Z			GG	0-0	33-22-22	D15318		5			D15366	5			YN501
2058B	24	PL	GH	4-9	33-22-22	D15318		4			D15366	4			YN501
2058R	24	PL	GH	0-0	33-22-22	D15318		3			D15366	3			YN501

WIRE LIST

D280A108

91-21-11

Section W3160

Page 11 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To				
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3170		286A3170				AB0420A TO E2-2 SHELF									
I	0501	24	PK		18-7	29-31-11	D49994P	A04			D40734P	18			YC051-YC055
I	0501	24	PK		18-5	29-31-11	D49994P	A04			D40734P	18			YC056-YR328
	0502	24	PK		18-7	29-31-11	D49994P	B04			D40734P	19			YC051-YC055
I	0502	24	PK		18-5	29-31-11	D49994P	B04			D40734P	19			YC056-YR328
	0503	24	PK		18-7	29-31-11	D49994P	A05			D40734P	20			YC051-YC055
I	0503	24	PK		18-5	29-31-11	D49994P	A05			D40734P	20			YC056-YR328
	1301R	20	X5	EN	17-6	26-11-11	D40126P	A09			D40734P	23			YC051-YC055
I	1301R	20	X5	EN	17-7	26-11-11	D40126P	A09			D40734P	23			YC056-YR328
I	1301Z			EN	0-0	26-11-11	D40126P	PERG	1F		D40734P	S/R			ALL
	1302R	20	X5	EP	17-6	26-11-11	D40126P	B09			D40734P	22			YC051-YC055
I	1302R	20	X5	EP	17-7	26-11-11	D40126P	B09			D40734P	22			YC056-YR328
I	1302Z			EP	0-0	26-11-11	D40126P	PERG	1F		D40734P	S/R			ALL
	2601B	20	PB	SA	17-6	SPARE	D40126P	A01			D40734P	1			YC051-YC055
I	2601B	20	PB	SA	17-7	SPARE	D40126P	A01			D40734P	1			YC056-YR328
I	2601R	20	PB	SA	0-0	SPARE	D40126P	B01			D40734P	2			ALL
	2602B	20	PB	SB	17-6	SPARE	D40126P	A02			D40734P	3			YC051-YC055
I	2602B	20	PB	SB	17-7	SPARE	D40126P	A02			D40734P	3			YC056-YR328
I	2602R	20	PB	SB	0-0	SPARE	D40126P	B02			D40734P	4			ALL
	2603B	20	PB	SC	17-6	SPARE	D40126P	A03			D40734P	5			YC051-YC055
I	2603B	20	PB	SC	17-7	SPARE	D40126P	A03			D40734P	5			YC056-YR328
I	2603R	20	PB	SC	0-0	SPARE	D40126P	B03			D40734P	6			ALL
	2604B	22	VX	SD	17-6	77-31-11	D40126P	A04			D40734P	7			YC051-YC055
I	2604B	22	VX	SD	17-7	77-31-11	D40126P	A04			D40734P	7			YC056-YR328
I	2604W	22	VX	SD	0-0	77-31-11	D40126P	B04			D40734P	8			ALL
I	2604Z			SD	0-0	77-31-11	D40126P	A05			D40734P	9			ALL
	2605B	24	Y2	SE	18-7	77-12-11	D49994P	B01			D40734P	16			YC051-YC055
I	2605B	24	Y2	SE	18-5	77-12-11	D49994P	B01			D40734P	16			YC056-YR328
I	2605R	24	Y2	SE	0-0	77-12-11	D49994P	A01			D40734P	15			ALL
I	2605Z			SE	0-0	77-12-11	D49994P	PERG	1F		D40734P	S/R			ALL
	2606B	20	X2	SF	18-7	SPARE	D49994P	A07			D40736P	1			YC051-YC055
I	2606B	20	X2	SF	18-5	SPARE	D49994P	A07			D40736P	1			YC056-YR328
I	2606R	20	X2	SF	0-0	SPARE	D49994P	B06			D40736P	2			ALL
I	2606Z			SF	0-0	SPARE	D49994P	PERG	1F		D40736P	S/R			ALL
	2607B	20	X2	SG	17-6	SPARE	D40126P	A11			D40736P	4			YC051-YC055
I	2607B	20	X2	SG	17-8	SPARE	D40126P	A11			D40736P	4			YC056-YR328
I	2607R	20	X2	SG	0-0	SPARE	D40126P	B11			D40736P	5			ALL
I	2607Z			SG	0-0	SPARE	D40126P	PERG	1F		D40736P	S/R			ALL
	2608B	22	PB	SH	17-6	78-36-11	D40126P	A12			D40736P	7			YC051-YC055
I	2608B	22	PB	SH	17-8	78-36-11	D40126P	A12			D40736P	7			YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W3170

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3170		286A3170			AB0420A TO E2-2 SHELF (continued)											
2608R		22		PB	SH	0-0	78-36-11	D40126P		B12		D40736P		8		ALL
2609B		22		PB	SJ	17-6	78-36-11	D40126P		A13		D40736P		9		YC051-YC055
2609B		22		PB	SJ	17-8	78-36-11	D40126P		A13		D40736P		9		YC056-YR328
2609R		22		PB	SJ	0-0	78-36-11	D40126P		B13		D40736P		10		ALL
2610B		24		Y2	SK	17-6	73-24-11	D40126P		A14		D40736P		11		YC051-YC055
2610B		24		Y2	SK	17-8	73-24-11	D40126P		A14		D40736P		11		YC056-YR328
2610R		24		Y2	SK	0-0	73-24-11	D40126P		B14		D40736P		12		ALL
2610Z					SK	0-0	73-24-11	D40126P		PERG	1F	D40736P		S/R		ALL
2611B		24		Y2	SL	18-7	73-24-12	D49994P		A06		D40736P		13		YC051-YC055
2611B		24		Y2	SL	18-5	73-24-12	D49994P		A06		D40736P		13		YC056-YR328
2611R		24		Y2	SL	0-0	73-24-12	D49994P		B05		D40736P		14		ALL
2611Z					SL	0-0	73-24-12	D49994P		PERG	1F	D40736P		S/R		ALL
3601B		24		Y3	A4	18-7	79-31-11	D49994P		A03		D40734P		12		YC051-YC055
3601B		24		Y3	A4	18-5	79-31-11	D49994P		A03		D40734P		12		YC056-YR328
3601R		24		Y3	A4	0-0	79-31-11	D49994P		A02		D40734P		13		ALL
3601Y		24		Y3	A4	0-0	79-31-11	D49994P		B02		D40734P		14		ALL
3601Z					A4	0-0	79-31-11	D49994P		PERG	1F	D40734P		S/R		ALL
6501		24		PK		18-7	31-62-14	D49994P		B03		D40734P		17		YC051-YC055
6501		24		PK		18-5	31-62-14	D49994P		B03		D40734P		17		YC056-YR328
6502		24		PK		18-7	31-62-14	D40734P		24		D49994P		B07		YC051-YC055
6502		24		PK		18-5	31-62-14	D40734P		24		D49994P		B07		YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W3170

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3192	286A3192				NS/FSB SIGN-VIDEO PANEL, FORWARD-LEFT										
3201B	20	PC	YA		4-6	33-25-51	D12011		2		SM00201		S		YL951-YL999
3201B	20	PC	YA		4-9	33-25-51	D12011		2		SM00201		S		YN231-YN260
3201R	20	PC	YA		0-0	33-25-51	D12011		1		SM00101		S		YL951-YN260
3201Y	20	PC	YA		0-0	33-25-51	D12011		3		SM00301		S		YL951-YN260
3203B	20	PC	YC		6-5	33-25-51	D12023		2		SM00203		S		YL951-YN260
3203R	20	PC	YC		0-0	33-25-51	D12023		1		SM00103		S		YL951-YN260
3203Y	20	PC	YC		0-0	33-25-51	D12023		3		SM00303		S		YL951-YN260
3205B	20	PC	YE		6-0	33-25-51	D12035		2		SM00205		S		YL951-YL999
3205B	20	PC	YE		6-1	33-25-51	D12035		2		SM00205		S		YN231-YN260
3205R	20	PC	YE		0-0	33-25-51	D12035		1		SM00105		S		YL951-YN260
3205Y	20	PC	YE		0-0	33-25-51	D12035		3		SM00305		S		YL951-YN260
3207B	20	PC	YG		4-10	33-25-51	D12047		2		SM00207		S		YL951-YL999
3207R	20	PC	YG		0-0	33-25-51	D12047		1		SM00107		S		YL951-YL999
3207Y	20	PC	YG		0-0	33-25-51	D12047		3		SM00307		S		YL951-YL999
3209B	20	PC	YI		5-1	33-25-51	D12059		2		SM00209		S		YL951-YL999
3209B	20	PC	YI		6-9	33-25-51	D12059		2		SM00209		S		YN231-YN260
3209R	20	PC	YI		0-0	33-25-51	D12059		1		SM00109		S		YL951-YN260
3209Y	20	PC	YI		0-0	33-25-51	D12059		3		SM00309		S		YL951-YN260
3211B	20	PC	YK		4-3	33-25-51	D12071		2		SM00211		S		YL951-YL999
3211B	20	PC	YK		12-9	33-25-51	D12071		2		SM00209		S		YN231-YN260
3211R	20	PC	YK		0-0	33-25-51	D12071		1		SM00111		S		YL951-YL999
3211R	20	PC	YK		0-0	33-25-51	D12071		1		SM00109		S		YN231-YN260
3211Y	20	PC	YK		0-0	33-25-51	D12071		3		SM00311		S		YL951-YL999
3211Y	20	PC	YK		0-0	33-25-51	D12071		3		SM00309		S		YN231-YN260
3213B	20	PC	YM		11-5	33-25-51	D12083		2		SM00211		S		YL951-YL999
3213R	20	PC	YM		0-0	33-25-51	D12083		1		SM00111		S		YL951-YL999
3213Y	20	PC	YM		0-0	33-25-51	D12083		3		SM00311		S		YL951-YL999
3215B	20	PC	YP		2-9	33-25-51	D40762J		2		SM00201		S		YL951-YL999
3215B	20	PC	YP		2-8	33-25-51	D40762J		2		SM00201		S		YN231-YN260
3215R	20	PC	YP		0-0	33-25-51	D40762J		1		SM00101		S		YL951-YN260
3215Y	20	PC	YP		0-0	33-25-51	D40762J		3		SM00301		S		YL951-YN260
3217B	20	PC	YR		4-9	33-25-51	SM00201			S	SM00203		S		YL951-YL999
3217B	20	PC	YR		4-7	33-25-51	SM00201			S	SM00203		S		YN231-YN260
3217R	20	PC	YR		0-0	33-25-51	SM00101			S	SM00103		S		YL951-YN260
3217Y	20	PC	YR		0-0	33-25-51	SM00301			S	SM00303		S		YL951-YN260
3219B	20	PC	YT		5-4	33-25-51	SM00203			S	SM00205		S		YL951-YL999
3219B	20	PC	YT		5-2	33-25-51	SM00203			S	SM00205		S		YN231-YN260
3219R	20	PC	YT		0-0	33-25-51	SM00103			S	SM00105		S		YL951-YN260
3219Y	20	PC	YT		0-0	33-25-51	SM00303			S	SM00305		S		YL951-YN260

WIRE LIST

D280A108

91-21-11

Section W3190

Page 1

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Diagram	From	To								
	Wire No.	GA	CO TY			Fam	FT-IN	Equip	Term	Type	Splice	Equip	Term	Type	Splice
W3192	286A3192			NS/FSB SIGN-VIDEO PANEL, FORWARD-LEFT (continued)											
3221B	20	PC	YV		3-3	33-25-51	SM00205		S		SM00207		S		YL951-YL999
3221R	20	PC	YV		0-0	33-25-51	SM00105		S		SM00107		S		YL951-YL999
3221Y	20	PC	YV		0-0	33-25-51	SM00305		S		SM00307		S		YL951-YL999
3223B	20	PC	YX		4-9	33-25-51	SM00207		S		SM00209		S		YL951-YL999
3223B	20	PC	YX		6-1	33-25-51	SM00205		S		SM00209		S		YN231-YN260
3223R	20	PC	YX		0-0	33-25-51	SM00107		S		SM00109		S		YL951-YL999
3223R	20	PC	YX		0-0	33-25-51	SM00105		S		SM00109		S		YN231-YN260
3223Y	20	PC	YX		0-0	33-25-51	SM00307		S		SM00309		S		YL951-YL999
3223Y	20	PC	YX		0-0	33-25-51	SM00305		S		SM00309		S		YN231-YN260
3225B	20	PC	YZ		8-5	33-25-51	SM00209		S		SM00211		S		YL951-YL999
3225R	20	PC	YZ		0-0	33-25-51	SM00109		S		SM00111		S		YL951-YL999
3225Y	20	PC	YZ		0-0	33-25-51	SM00309		S		SM00311		S		YL951-YL999
W3194	286A3194			NS/FSB SIGN-VIDEO PANEL, AFT-LEFT											
3201B	20	PC	YA		3-3	33-25-51	D12095	2			SM00201		S		YL951-YL999
3201B	20	PC	YA		3-7	33-25-51	D12095	2			SM00201		S		YN231-YN260
3201R	20	PC	YA		0-0	33-25-51	D12095	1			SM00101		S		YL951-YN260
3201Y	20	PC	YA		0-0	33-25-51	D12095	3			SM00301		S		YL951-YN260
3203B	20	PC	YC		4-6	33-25-51	D12107	2			SM00203		S		YL951-YL999
3203B	20	PC	YC		4-10	33-25-51	D12107	2			SM00203		S		YN231-YN260
3203R	20	PC	YC		0-0	33-25-51	D12107	1			SM00103		S		YL951-YN260
3203Y	20	PC	YC		0-0	33-25-51	D12107	3			SM00303		S		YL951-YN260
3205B	20	PC	YE		4-6	33-25-51	D12119	2			SM00205		S		YL951-YL999
3205R	20	PC	YE		0-0	33-25-51	D12119	1			SM00105		S		YL951-YL999
3205Y	20	PC	YE		0-0	33-25-51	D12119	3			SM00305		S		YL951-YL999
3207B	20	PC	YG		6-0	33-25-51	D12131	2			SM00207		S		YL951-YL999
3207B	20	PC	YG		5-1	33-25-51	D12131	2			SM00207		S		YN231-YN260
3207R	20	PC	YG		0-0	33-25-51	D12131	1			SM00107		S		YL951-YN260
3207Y	20	PC	YG		0-0	33-25-51	D12131	3			SM00307		S		YL951-YN260
3209B	20	PC	YI		6-1	33-25-51	D12143	2			SM00209		S		YL951-YL999
3209B	20	PC	YI		13-0	33-25-51	D12143	2			SM00207		S		YN231-YN260
3209R	20	PC	YI		0-0	33-25-51	D12143	1			SM00109		S		YL951-YL999
3209R	20	PC	YI		0-0	33-25-51	D12143	1			SM00107		S		YN231-YN260
3209Y	20	PC	YI		0-0	33-25-51	D12143	3			SM00309		S		YL951-YL999
3209Y	20	PC	YI		0-0	33-25-51	D12143	3			SM00307		S		YN231-YN260
3211B	20	PC	YK		11-3	33-25-51	D12155	2			SM00209		S		YL951-YL999
3211R	20	PC	YK		0-0	33-25-51	D12155	1			SM00109		S		YL951-YL999
3211Y	20	PC	YK		0-0	33-25-51	D12155	3			SM00309		S		YL951-YL999
3215B	20	PC	YP		2-8	33-25-51	D40764J	2			SM00201		S		YL951-YL999

WIRE LIST

D280A108

91-21-11

Section W3190

Page 2

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3194	286A3194			NS/FSB SIGN-VIDEO PANEL, AFT-LEFT (continued)											
3215B	20	PC	YP		2-0	33-25-51	D40764J				SM00201		S		YN231-YN260
3215R	20	PC	YP		0-0	33-25-51	D40764J				SM00101		S		YL951-YN260
3215Y	20	PC	YP		0-0	33-25-51	D40764J				SM00301		S		YL951-YN260
3217B	20	PC	YR		6-8	33-25-51	SM00201				SM00203		S		YL951-YL999
3217B	20	PC	YR		7-9	33-25-51	SM00201				SM00203		S		YN231-YN260
3217R	20	PC	YR		0-0	33-25-51	SM00101				SM00103		S		YL951-YN260
3217Y	20	PC	YR		0-0	33-25-51	SM00301				SM00303		S		YL951-YN260
3219B	20	PC	YT		6-1	33-25-51	SM00203				SM00205		S		YL951-YL999
3219R	20	PC	YT		0-0	33-25-51	SM00103				SM00105		S		YL951-YL999
3219Y	20	PC	YT		0-0	33-25-51	SM00303				SM00305		S		YL951-YL999
3221B	20	PC	YV		7-11	33-25-51	SM00205				SM00207		S		YL951-YL999
3221B	20	PC	YV		7-11	33-25-51	SM00203				SM00207		S		YN231-YN260
3221R	20	PC	YV		0-0	33-25-51	SM00105				SM00107		S		YL951-YL999
3221R	20	PC	YV		0-0	33-25-51	SM00103				SM00107		S		YN231-YN260
3221Y	20	PC	YV		0-0	33-25-51	SM00305				SM00307		S		YL951-YL999
3221Y	20	PC	YV		0-0	33-25-51	SM00303				SM00307		S		YN231-YN260
3223B	20	PC	YX		8-5	33-25-51	SM00207				SM00209		S		YL951-YL999
3223R	20	PC	YX		0-0	33-25-51	SM00107				SM00109		S		YL951-YL999
3223Y	20	PC	YX		0-0	33-25-51	SM00307				SM00309		S		YL951-YL999

WIRE LIST

D280A108

91-21-11

Section W3190

Page 3 End

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W3207	286A3207				FWD LT WALL MOUNT LCD MONITOR TO SIDEWALL DISCONNECT										
0001	20		PA		10-4	23-32-33	D10221		1		D10001J		1		YD157
0002	20		PA		10-4	23-32-33	D10221		2		D10001J		2		YD157
0003	22		PA		10-4	23-32-33	D10221		10		D10001J		10		YD157
0004	24		PK		10-4	23-32-33	D10221		6		D10001J		6		YD157
0005	22		PA		10-4	23-32-33	D10221		9		D10001J		9		YD157
0007	22		PA		10-4	23-32-33	D10221		4		D10001J		4		YD157
0008	22		PA		10-4	23-32-33	D10221		7		D10001J		7		YD157
0009	22		PA		10-4	23-32-33	D10221		8		D10001J		8		YD157
001CO				AA	0-0	23-32-33	D10221		= C1		D10003J		= C1		YD157
001CX		0F		AA	9-10	23-32-33	D10221		= A1	5M	D10003J		= A1		YD157

WIRE LIST

D280A108

91-21-11

Section W3200

Page 1 End

Aug 14/2012



WIRE LIST
D280A108

91-21-11
Section W3240
Page 1
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3246		286A3246			LED LIGHTING - SIDEWALL LEFT (continued)											
0024		18		PA		1-3	33-21-12	D14582		D		SM00005		S		YN501
0024		18		PA		2-2	33-21-12	D14582		D		SM00005		S		YR301-YR328
0025		18		PA		1-8	33-21-12	SM00005			S	GD03988	ST..	1		YN501
0025		18		PA		2-4	33-21-12	SM00005			S	GD03744	ST..	1		YR301-YR328
0026		18		PA		2-0	33-21-12	SM00005			S	GD00215	ST..	E		YN501
0026		18		PA		4-5	33-21-12	SM00005			S	GD00229	ST..	E		YR301-YR328
0031		18		PA		20-2	33-21-12	D14584		B		SM00002		S		YN501
0031		18		PA		6-2	33-21-12	D14584		B		SM00002		S		YR301-YR328
0032		18		PA		2-6	33-21-12	D14584		C		GD03988	AC..	1		YN501
0032		18		PA		2-10	33-21-12	D14584		C		GD03744	AC..	1		YR301-YR328
0033		18		PA		2-6	33-21-12	D14584		A		GD03988	ST..	1		YN501
0033		18		PA		2-10	33-21-12	D14584		A		GD03744	ST..	1		YR301-YR328
0034		18		PA		1-5	33-21-12	D14584		D		SM00004		S		YN501
0034		18		PA		2-6	33-21-12	D14584		D		SM00004		S		YR301-YR328
0035		18		PA		1-8	33-21-12	SM00004			S	GD03988	ST..	1		YN501
0035		18		PA		1-0	33-21-12	SM00004			S	GD03744	ST..	1		YR301-YR328
0036		18		PA		3-1	33-21-12	SM00004			S	GD00211	ST..	E		YN501
0036		18		PA		3-8	33-21-12	SM00004			S	GD00211	ST..	E		YR301-YR328
0041		18		PA		21-6	33-21-12	D14586		B		SM00003		S		YN501
0041		18		PA		6-7	33-21-12	D14586		B		SM00003		S		YR301-YR328
0042		18		PA		5-2	33-21-12	D14586		C		GD04006	AC..	1		YN501
0042		18		PA		5-1	33-21-12	D14586		C		GD04006	AC..	1		YR301-YR328
0043		18		PA		5-2	33-21-12	D14586		A		GD04006	ST..	1		YN501
0043		18		PA		5-1	33-21-12	D14586		A		GD04006	ST..	1		YR301-YR328
0044		18		PA		5-2	33-21-12	D14586		D		GD04006	ST..	1		YN501
0044		18		PA		5-1	33-21-12	D14586		D		GD04006	ST..	1		YR301-YR328
0051		18		PA		21-6	33-21-12	D14588		B		SM00003		S		YN501
0051		18		PA		6-7	33-21-12	D14588		B		SM00003		S		YR301-YR328
0052		18		PA		5-2	33-21-12	D14588		C		GD04006	AC..	1		YN501
0052		18		PA		5-1	33-21-12	D14588		C		GD04006	AC..	1		YR301-YR328
0053		18		PA		5-2	33-21-12	D14588		A		GD04006	ST..	1		YN501
0053		18		PA		5-1	33-21-12	D14588		A		GD04006	ST..	1		YR301-YR328
0054		18		PA		5-2	33-21-12	D14588		D		GD04006	ST..	1		YN501
0054		18		PA		5-1	33-21-12	D14588		D		GD04006	ST..	1		YR301-YR328
2001B		24		OT	EA	17-2	33-21-12	D14668		2		D14590		2		YN501-YR328
2001W		24		OT	EA	0-0	33-21-12	D14668		1		D14590		1		YN501-YR328
2001Z					EA	0-0	33-21-12	D14668		5		D14590		5		YN501-YR328
2002B		24		PL	EB	17-2	33-21-12	D14668		4		D14590		4		YN501-YR328
2002R		24		PL	EB	0-0	33-21-12	D14668		3		D14590		3		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W3240

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3249	286A3249			PSU LCD VIDEO MONITOR (STA 350R TO STA 400R) TO VDU IN TRAY 1 (-800)											
0001	20		PA		19-9	23-32-31	D10207		1		D12013		1		YL951-YL999
0001	20		PA		20-0	23-32-31	D10207		1		D12013		1		YN231-YN260
0002	20		PA		19-9	23-32-31	D10207		2		D12013		4		YL951-YL999
0002	20		PA		20-0	23-32-31	D10207		2		D12013		4		YN231-YN260
0003	22		PA		19-9	23-32-31	D10207		10		D12013		2		YL951-YL999
0003	22		PA		20-0	23-32-31	D10207		10		D12013		2		YN231-YN260
0004	24		PK		19-9	23-32-31	D10207		6		D12013		8		YL951-YL999
0004	24		PK		20-0	23-32-31	D10207		6		D12013		8		YN231-YN260
0005	22		PA		19-1	23-32-31	D10207		9		SM00001			S	YL951-YL999
0005	22		PA		19-4	23-32-31	D10207		9		SM00001			S	YN231-YN260
0006	20		PA		19-9	23-32-31	D10207		4		D12013		5		YL951-YL999
0006	20		PA		20-0	23-32-31	D10207		4		D12013		5		YN231-YN260
0007	22		PA		1-3	23-32-31	D12013		3		SM00001			S	YL951-YN260
0008	22		PA		1-3	23-32-31	D12013		6		SM00001			S	YL951-YN260
0009	22		PA		1-3	23-32-31	D12013		7		SM00001			S	YL951-YN260
001CO				AA	0-0	23-32-31	D10207		= C1		D12015		= C1		YL951-YN260
001CX		0F		AA	19-3	23-32-31	D10207		= A1	5M	D12015		= A1		YL951-YL999
001CX		0F		AA	19-6	23-32-31	D10207		= A1	5M	D12015		= A1		YN231-YN260

WIRE LIST

D280A108

91-21-11
Section W3240
Page 3 End
Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Diagram	From				To				Effectivity	
	Wire No.	GA	CO TY			Fam	FT-IN	Equip	Term	Type	Splice	Equip	Term		Type
W3251	286A3251			PSU LCD VIDEO MONITOR (STA 396L TO STA 490L) TO VDU IN TRAY 1 (-800)											
0001	20	PA			14-6	23-32-32	D10213		1		D12019		1		YL951-YL999
0001	20	PA			14-4	23-32-32	D10213		1		D12019		1		YN231-YN260
0002	20	PA			14-6	23-32-32	D10213		2		D12019		4		YL951-YL999
0002	20	PA			14-4	23-32-32	D10213		2		D12019		4		YN231-YN260
0003	22	PA			14-6	23-32-32	D10213		10		D12019		2		YL951-YL999
0003	22	PA			14-4	23-32-32	D10213		10		D12019		2		YN231-YN260
0004	24	PK			14-6	23-32-32	D10213		6		D12019		8		YL951-YL999
0004	24	PK			14-4	23-32-32	D10213		6		D12019		8		YN231-YN260
0005	22	PA		AA	13-10	23-32-32	D10213		9		SM00001			S	YL951-YL999
0005	22	PA		AA	13-8	23-32-32	D10213		9		SM00001			S	YN231-YN260
0006	20	PA			14-6	23-32-32	D10213		4		D12019		5		YL951-YL999
0006	20	PA			14-4	23-32-32	D10213		4		D12019		5		YN231-YN260
0007	22	PA			1-3	23-32-32	D12019		3		SM00001			S	YL951-YN260
0008	22	PA			1-3	23-32-32	D12019		6		SM00001			S	YL951-YN260
0009	22	PA			1-3	23-32-32	D12019		7		SM00001			S	YL951-YN260
001CO			AA		0-0	23-32-32	D10213		=C1		D12021		=C1		YL951-YN260
001CX		OF	AA		14-0	23-32-32	D10213		=A1	5M	D12021		=A1		YL951-YL999
001CX		OF	AA		13-10	23-32-32	D10213		=A1	5M	D12021		=A1		YN231-YN260
W3253	286A3253			PSU LCD VIDEO MONITOR (STA 396R TO 490R) TO VDU IN TRAY 1 (-800)											
0001	20	PA			19-6	23-32-32	D10215		1		D12025		1		YL951-YL999
0001	20	PA			19-8	23-32-32	D10215		1		D12025		1		YN231-YN260
0002	20	PA			19-6	23-32-32	D10215		2		D12025		4		YL951-YL999
0002	20	PA			19-8	23-32-32	D10215		2		D12025		4		YN231-YN260
0003	22	PA			19-6	23-32-32	D10215		10		D12025		2		YL951-YL999
0003	22	PA			19-8	23-32-32	D10215		10		D12025		2		YN231-YN260
0004	24	PK			19-6	23-32-32	D10215		6		D12025		8		YL951-YL999
0004	24	PK			19-8	23-32-32	D10215		6		D12025		8		YN231-YN260
0005	22	PA			18-10	23-32-32	D10215		9		SM00001			S	YL951-YL999
0005	22	PA			19-0	23-32-32	D10215		9		SM00001			S	YN231-YN260
0006	20	PA			19-6	23-32-32	D10215		4		D12025		5		YL951-YL999
0006	20	PA			19-8	23-32-32	D10215		4		D12025		5		YN231-YN260
0007	22	PA			1-3	23-32-32	D12025		3		SM00001			S	YL951-YN260
0008	22	PA			1-3	23-32-32	D12025		6		SM00001			S	YL951-YN260
0009	22	PA			1-3	23-32-32	D12025		7		SM00001			S	YL951-YN260
001CO			AA		0-0	23-32-32	D10215		=C1		D12027		=C1		YL951-YN260
001CX		OF	AA		19-0	23-32-32	D10215		=A1	5M	D12027		=A1		YL951-YL999
001CX		OF	AA		19-2	23-32-32	D10215		=A1	5M	D12027		=A1		YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W3250

Page 1

Aug 14/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
PSU LCD VIDEO MONITOR (STA 455L TO STA 500B+1L) TO VDU IN TRAY 1(-800)																
W3255	286A3255															
0001	20		PA		16-9	23-32-33	D10221		1			D12031		1		YL951-YL999
0001	20		PA		17-1	23-32-33	D10221		1			D12031		1		YN231-YN260
0002	20		PA		16-9	23-32-33	D10221		2			D12031		4		YL951-YL999
0002	20		PA		17-1	23-32-33	D10221		2			D12031		4		YN231-YN260
0003	22		PA		16-9	23-32-33	D10221		10			D12031		2		YL951-YL999
0003	22		PA		17-1	23-32-33	D10221		10			D12031		2		YN231-YN260
0004	24		PK		16-9	23-32-33	D10221		6			D12031		8		YL951-YL999
0004	24		PK		17-1	23-32-33	D10221		6			D12031		8		YN231-YN260
0005	22		PA		16-1	23-32-33	D10221		9			SM00001			S	YL951-YL999
0005	22		PA		16-5	23-32-33	D10221		9			SM00001			S	YN231-YN260
0006	20		PA		16-9	23-32-33	D10221		4			D12031		5		YL951-YL999
0006	20		PA		17-1	23-32-33	D10221		4			D12031		5		YN231-YN260
0007	22		PA		1-3	23-32-33	D12031		3			SM00001			S	YL951-YN260
0008	22		PA		1-3	23-32-33	D12031		6			SM00001			S	YL951-YN260
0009	22		PA		1-3	23-32-33	D12031		7			SM00001			S	YL951-YN260
001CO				AA	0-0	23-32-33	D10221		=C1			D12033		=C1		YL951-YN260
001CX			OF	AA	16-3	23-32-33	D10221		=A1	5M		D12033		=A1		YL951-YL999
001CX			OF	AA	16-7	23-32-33	D10221		=A1	5M		D12033		=A1		YN231-YN260
PSU LCD VIDEO MONITOR (STA 455R TO STA 500B+1R) TO VDU IN TRAY 1(-800)																
W3257	286A3257															
0001	20		PA		25-1	23-32-33	D10223		1			D12037		1		YL951-YL999
0001	20		PA		24-10	23-32-33	D10223		1			D12037		1		YN231-YN260
0002	20		PA		25-1	23-32-33	D10223		2			D12037		4		YL951-YL999
0002	20		PA		24-10	23-32-33	D10223		2			D12037		4		YN231-YN260
0003	22		PA		25-1	23-32-33	D10223		10			D12037		2		YL951-YL999
0003	22		PA		24-10	23-32-33	D10223		10			D12037		2		YN231-YN260
0004	24		PK		25-1	23-32-33	D10223		6			D12037		8		YL951-YL999
0004	24		PK		24-10	23-32-33	D10223		6			D12037		8		YN231-YN260
0005	22		PA		24-5	23-32-33	D10223		9			SM00001			S	YL951-YL999
0005	22		PA		24-2	23-32-33	D10223		9			SM00001			S	YN231-YN260
0006	20		PA		25-1	23-32-33	D10223		4			D12037		5		YL951-YL999
0006	20		PA		24-10	23-32-33	D10223		4			D12037		5		YN231-YN260
0007	22		PA		1-3	23-32-33	D12037		3			SM00001			S	YL951-YN260
0008	22		PA		1-3	23-32-33	D12037		6			SM00001			S	YL951-YN260
0009	22		PA		1-3	23-32-33	D12037		7			SM00001			S	YL951-YN260
001CO				AA	0-0	23-32-33	D10223		=C1			D12039		=C1		YL951-YN260
001CX			OF	AA	24-7	23-32-33	D10223		=A1	5M		D12039		=A1		YL951-YL999
001CX			OF	AA	24-4	23-32-33	D10223		=A1	5M		D12039		=A1		YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W3250

Page 2

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3259	286A3259			PSU LCD VIDEO MONITOR(STA 500L TO STA 500B+16L) TO VDU IN TRAY 1(-800)											
0001	20		PA		17-6	23-32-34	D10229		1		D12043		1		YL951-YL999
0002	20		PA		17-6	23-32-34	D10229		2		D12043		4		YL951-YL999
0003	22		PA		17-6	23-32-34	D10229		10		D12043		2		YL951-YL999
0004	24		PK		17-6	23-32-34	D10229		6		D12043		8		YL951-YL999
0005	22		PA		16-10	23-32-34	D10229		9		SM00001			S	YL951-YL999
0006	20		PA		17-6	23-32-34	D10229		4		D12043		5		YL951-YL999
0007	22		PA		1-3	23-32-34	D12043		3		SM00001			S	YL951-YL999
0008	22		PA		1-3	23-32-34	D12043		6		SM00001			S	YL951-YL999
0009	22		PA		1-3	23-32-34	D12043		7		SM00001			S	YL951-YL999
001CO				AA	0-0	23-32-34	D10229		= C1		D12045		= C1		YL951-YL999
001CX				0F AA	17-0	23-32-34	D10229		= A1	5M	D12045		= A1		YL951-YL999

WIRE LIST

D280A108

91-21-11

Section W3250

Page 3 End

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3261	286A3261				PSU LCD VIDEO MONITOR(STA 500R TO STA 500B+16R) TO VDU IN TRAY 1(-800)										
0001	20		PA		27-4	23-32-34	D10231		1		D12049		1		YL951-YL999
0002	20		PA		27-4	23-32-34	D10231		2		D12049		4		YL951-YL999
0003	22		PA		27-4	23-32-34	D10231		10		D12049		2		YL951-YL999
0004	24		PK		27-4	23-32-34	D10231		6		D12049		8		YL951-YL999
0005	22		PA		26-8	23-32-34	D10231		9		SM00001			S	YL951-YL999
0006	20		PA		27-4	23-32-34	D10231		4		D12049		5		YL951-YL999
0007	22		PA		1-3	23-32-34	D12049		3		SM00001			S	YL951-YL999
0008	22		PA		1-3	23-32-34	D12049		6		SM00001			S	YL951-YL999
0009	22		PA		1-3	23-32-34	D12049		7		SM00001			S	YL951-YL999
001CO				AA	0-0	23-32-34	D10231		=C1		D12051		=C1		YL951-YL999
001CX				OF AA	26-10	23-32-34	D10231		=A1	5M	D12051		=A1		YL951-YL999
W3263	286A3263				PSU LCD VIDEO MONITOR(STA 500A+18L TO 500E+10L) TO VDU IN TRAY 2(-800)										
0001	20		PA		19-3	23-32-41	D10237		1		D12055		1		YL951-YL999
0001	20		PA		18-5	23-32-41	D10237		1		D12055		1		YN231-YN260
0002	20		PA		19-3	23-32-41	D10237		2		D12055		4		YL951-YL999
0002	20		PA		18-5	23-32-41	D10237		2		D12055		4		YN231-YN260
0003	22		PA		19-3	23-32-41	D10237		10		D12055		2		YL951-YL999
0003	22		PA		18-5	23-32-41	D10237		10		D12055		2		YN231-YN260
0004	24		PK		19-3	23-32-41	D10237		6		D12055		8		YL951-YL999
0004	24		PK		18-5	23-32-41	D10237		6		D12055		8		YN231-YN260
0005	22		PA		18-7	23-32-41	D10237		9		SM00001			S	YL951-YL999
0005	22		PA		17-9	23-32-41	D10237		9		SM00001			S	YN231-YN260
0006	20		PA		19-3	23-32-41	D12055		5		D10237		4		YL951-YL999
0006	20		PA		18-5	23-32-41	D12055		5		D10237		4		YN231-YN260
0007	22		PA		1-2	23-32-41	D12055		3		SM00001			S	YL951-YL999
0007	22		PA		1-3	23-32-41	D12055		3		SM00001			S	YN231-YN260
0008	22		PA		1-2	23-32-41	D12055		6		SM00001			S	YL951-YL999
0008	22		PA		1-3	23-32-41	D12055		6		SM00001			S	YN231-YN260
0009	22		PA		1-2	23-32-41	D12055		7		SM00001			S	YL951-YL999
0009	22		PA		1-3	23-32-41	D12055		7		SM00001			S	YN231-YN260
001CO				AA	0-0	23-32-41	D10237		=C1		D12057		=C1		YL951-YN260
001CX				OF AA	18-9	23-32-41	D10237		=A1	5M	D12057		=A1		YL951-YL999
001CX				OF AA	17-11	23-32-41	D10237		=A1	5M	D12057		=A1		YN231-YN260
W3265	286A3265				PSU LCD VIDEO MONITOR(STA 500A+18R TO 500E+10R) TO VDU IN TRAY 2(-800)										
0001	20		PA		23-5	23-32-41	D10239		1		D12061		1		YL951-YL999
0001	20		PA		23-2	23-32-41	D10239		1		D12061		1		YN231-YN260
0002	20		PA		23-5	23-32-41	D10239		2		D12061		4		YL951-YL999

WIRE LIST

D280A108

91-21-11

Section W3260

Page 1

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W3265	286A3265				PSU LCD VIDEO MONITOR(STA 500A+18R TO 500E+10R) TO VDU IN TRAY 2(-800) (continued)											
0002	20		PA		23-2	23-32-41	D10239		2			D12061	4			YN231-YN260
0003	22		PA		23-5	23-32-41	D10239		10			D12061	2			YL951-YL999
0003	22		PA		23-2	23-32-41	D10239		10			D12061	2			YN231-YN260
0004	24		PK		23-5	23-32-41	D10239		6			D12061	8			YL951-YL999
0004	24		PK		23-2	23-32-41	D10239		6			D12061	8			YN231-YN260
0005	22		PA		22-9	23-32-41	D10239		9			SM00001		S		YL951-YL999
0005	22		PA		22-6	23-32-41	D10239		9			SM00001		S		YN231-YN260
0006	20		PA		23-5	23-32-41	D12061		5			D10239	4			YL951-YL999
0006	20		PA		23-2	23-32-41	D12061		5			D10239	4			YN231-YN260
0007	22		PA		1-3	23-32-41	D12061		3			SM00001		S		YL951-YN260
0008	22		PA		1-3	23-32-41	D12061		6			SM00001		S		YL951-YN260
0009	22		PA		1-3	23-32-41	D12061		7			SM00001		S		YL951-YN260
001CO				AA	0-0	23-32-41	D10239		=C1			D12063	=C1			YL951-YN260
001CX		0F		AA	22-11	23-32-41	D10239		=A1	5M		D12063	=A1			YL951-YL999
001CX		0F		AA	22-8	23-32-41	D10239		=A1	5M		D12063	=A1			YN231-YN260
W3267	286A3267				PSU LCD VIDEO MONITOR(STA 500E+20L TO 500H+14L) TO VDU IN TRAY 2(-800)											
0001	20		PA		8-11	23-32-42	D10245		1			D12067	1			YL951-YL999
0001	20		PA		9-2	23-32-42	D10245		1			D12067	1			YN231-YN260
0002	20		PA		8-11	23-32-42	D10245		2			D12067	4			YL951-YL999
0002	20		PA		9-2	23-32-42	D10245		2			D12067	4			YN231-YN260
0003	22		PA		8-11	23-32-42	D10245		10			D12067	2			YL951-YL999
0003	22		PA		9-2	23-32-42	D10245		10			D12067	2			YN231-YN260
0004	24		PK		8-11	23-32-42	D10245		6			D12067	8			YL951-YL999
0004	24		PK		9-2	23-32-42	D10245		6			D12067	8			YN231-YN260
0005	22		PA		8-3	23-32-42	D10245		9			SM00001		S		YL951-YL999
0005	22		PA		8-6	23-32-42	D10245		9			SM00001		S		YN231-YN260
0006	20		PA		8-11	23-32-42	D12067		5			D10245	4			YL951-YL999
0006	20		PA		9-2	23-32-42	D12067		5			D10245	4			YN231-YN260
0007	22		PA		1-3	23-32-42	D12067		3			SM00001		S		YL951-YN260
0008	22		PA		1-3	23-32-42	D12067		6			SM00001		S		YL951-YN260
0009	22		PA		1-3	23-32-42	D12067		7			SM00001		S		YL951-YN260
001CO				AA	0-0	23-32-42	D10245		=C1			D12069	=C1			YL951-YN260
001CX		0F		AA	8-5	23-32-42	D10245		=A1	5M		D12069	=A1			YL951-YL999
001CX		0F		AA	8-8	23-32-42	D10245		=A1	5M		D12069	=A1			YN231-YN260
W3269	286A3269				PSU LCD VIDEO MONITOR(STA 500E+20R TO 500H+14R) TO VDU IN TRAY 2(-800)											
0001	20		PA		22-1	23-32-42	D10247		1			D12073	1			YL951-YL999
0001	20		PA		22-3	23-32-42	D10247		1			D12073	1			YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W3260

Page 2

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3269	286A3269			PSU LCD VIDEO MONITOR(STA 500E+20R TO 500H+14R) TO VDU IN TRAY 2(-800) (continued)											
0002	20		PA		22-1	23-32-42	D10247		2		D12073		4		YL951-YL999
0002	20		PA		22-3	23-32-42	D10247		2		D12073		4		YN231-YN260
0003	22		PA		22-1	23-32-42	D10247		10		D12073		2		YL951-YL999
0003	22		PA		22-3	23-32-42	D10247		10		D12073		2		YN231-YN260
0004	24		PK		22-1	23-32-42	D10247		6		D12073		8		YL951-YL999
0004	24		PK		22-3	23-32-42	D10247		6		D12073		8		YN231-YN260
0005	22		PA		21-5	23-32-42	D10247		9		SM00001			S	YL951-YL999
0005	22		PA		21-7	23-32-42	D10247		9		SM00001			S	YN231-YN260
0006	20		PA		22-1	23-32-42	D12073		5		D10247		4		YL951-YL999
0006	20		PA		22-3	23-32-42	D12073		5		D10247		4		YN231-YN260
0007	22		PA		1-3	23-32-42	D12073		3		SM00001			S	YL951-YN260
0008	22		PA		1-3	23-32-42	D12073		6		SM00001			S	YL951-YN260
0009	22		PA		1-3	23-32-42	D12073		7		SM00001			S	YL951-YN260
001CO				AA	0-0	23-32-42	D10247		= C1		D12075		= C1		YL951-YN260
001CX			0F	AA	21-7	23-32-42	D10247		= A1	5M	D12075		= A1		YL951-YL999
001CX			0F	AA	21-9	23-32-42	D10247		= A1	5M	D12075		= A1		YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W3260

Page 3 End

Aug 14/2012



WIRE LIST

91-21-11

Section W3270

Page 1

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W3275	286A3275				PSU LCD VIDEO MONITOR (STA 652L TO 688L) TO VDU IN TRAY 3(-800) (continued)										
0008	22		PA		1-3	23-32-51	D12091		6		SM00001		S		YL951-YN260
0009	22		PA		1-3	23-32-51	D12091		7		SM00001		S		YL951-YN260
001CO				AA	0-0	23-32-51	D10269		= C1		D12093		= C1		YL951-YN260
001CX			OF	AA	16-0	23-32-51	D10269		= A1	5M	D12093		= A1		YL951-YL999
001CX			OF	AA	17-11	23-32-51	D10269		= A1	5M	D12093		= A1		YN231-YN260
W3277	286A3277				PSU LCD VIDEO MONITOR (STA 652R TO 688R) TO VDU IN TRAY 3(-800)										
0001	20		PA		23-6	23-32-51	D10271		1		D12097		1		YL951-YL999
0001	20		PA		19-5	23-32-51	D10271		1		D12097		1		YN231-YN260
0002	20		PA		23-6	23-32-51	D10271		2		D12097		4		YL951-YL999
0002	20		PA		19-5	23-32-51	D10271		2		D12097		4		YN231-YN260
0003	22		PA		23-6	23-32-51	D10271		10		D12097		2		YL951-YL999
0003	22		PA		19-5	23-32-51	D10271		10		D12097		2		YN231-YN260
0004	24		PK		23-6	23-32-51	D10271		6		D12097		8		YL951-YL999
0004	24		PK		19-5	23-32-51	D10271		6		D12097		8		YN231-YN260
0005	22		PA		22-10	23-32-51	D10271		9		SM00001		S		YL951-YL999
0005	22		PA		18-9	23-32-51	D10271		9		SM00001		S		YN231-YN260
0006	20		PA		23-6	23-32-51	D10271		4		D12097		5		YL951-YL999
0006	20		PA		19-5	23-32-51	D10271		4		D12097		5		YN231-YN260
0007	22		PA		1-3	23-32-51	D12097		3		SM00001		S		YL951-YN260
0008	22		PA		1-3	23-32-51	D12097		6		SM00001		S		YL951-YN260
0009	22		PA		1-3	23-32-51	D12097		7		SM00001		S		YL951-YN260
001CO				AA	0-0	23-32-51	D10271		= C1		D12099		= C1		YL951-YN260
001CX			OF	AA	23-0	23-32-51	D10271		= A1	5M	D12099		= A1		YL951-YL999
001CX			OF	AA	18-11	23-32-51	D10271		= A1	5M	D12099		= A1		YN231-YN260
W3279	286A3279				PSU LCD VIDEO MONITOR (STA 712L TO 727B+11L) TO VDU IN TRAY 3(-800)										
0001	20		PA		14-11	23-32-52	D10277		1		D12103		1		YL951-YL999
0001	20		PA		15-5	23-32-52	D10277		1		D12103		1		YN231-YN260
0002	20		PA		14-11	23-32-52	D10277		2		D12103		4		YL951-YL999
0002	20		PA		15-5	23-32-52	D10277		2		D12103		4		YN231-YN260
0003	22		PA		14-11	23-32-52	D10277		10		D12103		2		YL951-YL999
0003	22		PA		15-5	23-32-52	D10277		10		D12103		2		YN231-YN260
0004	24		PK		14-11	23-32-52	D10277		6		D12103		8		YL951-YL999
0004	24		PK		15-5	23-32-52	D10277		6		D12103		8		YN231-YN260
0005	22		PA		14-3	23-32-52	D10277		9		SM00001		S		YL951-YL999
0005	22		PA		14-9	23-32-52	D10277		9		SM00001		S		YN231-YN260
0006	20		PA		14-11	23-32-52	D10277		4		D12103		5		YL951-YL999
0006	20		PA		15-5	23-32-52	D10277		4		D12103		5		YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W3270

Page 2

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3279	286A3279			PSU LCD VIDEO MONITOR (STA 712L TO 727B+11L) TO VDU IN TRAY 3(-800) (continued)											
0007	22		PA		1-3	23-32-52	D12103		3		SM00001		S		YL951-YN260
0008	22		PA		1-3	23-32-52	D12103		6		SM00001		S		YL951-YN260
0009	22		PA		1-3	23-32-52	D12103		7		SM00001		S		YL951-YN260
001CO				AA	0-0	23-32-52	D10277	= C1			D12105	= C1			YL951-YN260
001CX		0F		AA	14-5	23-32-52	D10277	= A1	5M		D12105	= A1			YL951-YL999
001CX		0F		AA	14-11	23-32-52	D10277	= A1	5M		D12105	= A1			YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W3270

Page 3 End

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3281	286A3281			PSU LCD VIDEO MONITOR (STA 712R TO 727B+11R) TO VDU IN TRAY 3(-800)											
0001	20		PA		19-8	23-32-52	D10279		1		D12109		1		YL951-YL999
0001	20		PA		24-1	23-32-52	D10279		1		D12109		1		YN231-YN260
0002	20		PA		19-8	23-32-52	D10279		2		D12109		4		YL951-YL999
0002	20		PA		24-1	23-32-52	D10279		2		D12109		4		YN231-YN260
0003	22		PA		19-8	23-32-52	D10279		10		D12109		2		YL951-YL999
0003	22		PA		24-1	23-32-52	D10279		10		D12109		2		YN231-YN260
0004	24		PK		19-8	23-32-52	D10279		6		D12109		8		YL951-YL999
0004	24		PK		24-1	23-32-52	D10279		6		D12109		8		YN231-YN260
0005	22		PA		19-0	23-32-52	D10279		9		SM00001			S	YL951-YL999
0005	22		PA		23-5	23-32-52	D10279		9		SM00001			S	YN231-YN260
0006	20		PA		19-8	23-32-52	D10279		4		D12109		5		YL951-YL999
0006	20		PA		24-1	23-32-52	D10279		4		D12109		5		YN231-YN260
0007	22		PA		1-3	23-32-52	D12109		3		SM00001			S	YL951-YN260
0008	22		PA		1-3	23-32-52	D12109		6		SM00001			S	YL951-YN260
0009	22		PA		1-3	23-32-52	D12109		7		SM00001			S	YL951-YN260
001CO				AA	0-0	23-32-52	D10279		=C1		D12111		=C1		YL951-YN260
001CX			OF	AA	19-2	23-32-52	D10279		=A1	5M	D12111		=A1		YL951-YL999
001CX			OF	AA	23-7	23-32-52	D10279		=A1	5M	D12111		=A1		YN231-YN260
W3283	286A3283			PSU LCD VIDEO MONITOR (STA 727B+5L TO 727E+7L) TO VDU IN TRAY 3(-800)											
0001	20		PA		21-3	23-32-53	D10285		1		D12115		1		YL951-YL999
0002	20		PA		21-3	23-32-53	D10285		2		D12115		4		YL951-YL999
0003	22		PA		21-3	23-32-53	D10285		10		D12115		2		YL951-YL999
0004	24		PK		21-3	23-32-53	D10285		6		D12115		8		YL951-YL999
0005	22		PA		20-7	23-32-53	D10285		9		SM00001			S	YL951-YL999
0006	20		PA		21-3	23-32-53	D10285		4		D12115		5		YL951-YL999
0007	22		PA		1-3	23-32-53	D12115		3		SM00001			S	YL951-YL999
0008	22		PA		1-3	23-32-53	D12115		6		SM00001			S	YL951-YL999
0009	22		PA		1-3	23-32-53	D12115		7		SM00001			S	YL951-YL999
001CO				AA	0-0	23-32-53	D10285		=C1		D12117		=C1		YL951-YL999
001CX			OF	AA	20-9	23-32-53	D10285		=A1	5M	D12117		=A1		YL951-YL999
W3285	286A3285			PSU LCD VIDEO MONITOR (STA 727B+5R TO 727E+7R) TO VDU IN TRAY 3(-800)											
0001	20		PA		27-1	23-32-53	D10287		1		D12121		1		YL951-YL999
0002	20		PA		27-1	23-32-53	D10287		2		D12121		4		YL951-YL999
0003	22		PA		27-1	23-32-53	D10287		10		D12121		2		YL951-YL999
0004	24		PK		27-1	23-32-53	D10287		6		D12121		8		YL951-YL999
0005	22		PA		26-5	23-32-53	D10287		9		SM00001			S	YL951-YL999
0006	20		PA		27-1	23-32-53	D10287		4		D12121		5		YL951-YL999

WIRE LIST

D280A108

91-21-11

Section W3280

Page 1

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From	To			Effectivity						
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3285	286A3285			PSU LCD VIDEO MONITOR (STA 727B+5R TO 727E+7R) TO VDU IN TRAY 3(-800) (continued)											
0007	22		PA		1-3	23-32-53	D12121	3			SM00001		S		YL951-YL999
0008	22		PA		1-3	23-32-53	D12121	6			SM00001		S		YL951-YL999
0009	22		PA		1-3	23-32-53	D12121	7			SM00001		S		YL951-YL999
001CO				AA	0-0	23-32-53	D10287	=C1			D12123	=C1			YL951-YL999
001CX		0F		AA	26-7	23-32-53	D10287	=A1	5M		D12123	=A1			YL951-YL999
W3287	286A3287			PSU LCD VIDEO MONITOR (STA 727E+3L TO 727I+5L) TO VDU IN TRAY 4(-800)											
0001	20		PA		18-8	23-32-61	D10301	1			D12127	1			YL951-YL999
0001	20		PA		15-8	23-32-61	D10301	1			D12127	1			YN231-YN260
0002	20		PA		18-8	23-32-61	D10301	2			D12127	4			YL951-YL999
0002	20		PA		15-8	23-32-61	D10301	2			D12127	4			YN231-YN260
0003	22		PA		18-8	23-32-61	D10301	10			D12127	2			YL951-YL999
0003	22		PA		15-8	23-32-61	D10301	10			D12127	2			YN231-YN260
0004	24		PK		18-8	23-32-61	D10301	6			D12127	8			YL951-YL999
0004	24		PK		15-8	23-32-61	D10301	6			D12127	8			YN231-YN260
0005	22		PA		18-0	23-32-61	D10301	9			SM00001		S		YL951-YL999
0005	22		PA		15-0	23-32-61	D10301	9			SM00001		S		YN231-YN260
0006	20		PA		18-8	23-32-61	D10301	4			D12127	5			YL951-YL999
0006	20		PA		15-8	23-32-61	D10301	4			D12127	5			YN231-YN260
0007	22		PA		1-2	23-32-61	D12127	3			SM00001		S		YL951-YL999
0007	22		PA		1-3	23-32-61	D12127	3			SM00001		S		YN231-YN260
0008	22		PA		1-2	23-32-61	D12127	6			SM00001		S		YL951-YL999
0008	22		PA		1-3	23-32-61	D12127	6			SM00001		S		YN231-YN260
0009	22		PA		1-2	23-32-61	D12127	7			SM00001		S		YL951-YL999
0009	22		PA		1-3	23-32-61	D12127	7			SM00001		S		YN231-YN260
001CO				AA	0-0	23-32-61	D10301	=C1			D12129	=C1			YL951-YN260
001CX		0F		AA	18-2	23-32-61	D10301	=A1	5M		D12129	=A1			YL951-YL999
001CX		0F		AA	15-2	23-32-61	D10301	=A1	5M		D12129	=A1			YN231-YN260
W3289	286A3289			PSU LCD VIDEO MONITOR (STA 727E+3R TO 727I+5R) TO VDU IN TRAY 4(-800)											
0001	20		PA		22-4	23-32-61	D10303	1			D12133	1			YL951-YL999
0001	20		PA		17-9	23-32-61	D10303	1			D12133	1			YN231-YN260
0002	20		PA		22-4	23-32-61	D10303	2			D12133	4			YL951-YL999
0002	20		PA		17-9	23-32-61	D10303	2			D12133	4			YN231-YN260
0003	22		PA		22-4	23-32-61	D10303	10			D12133	2			YL951-YL999
0003	22		PA		17-9	23-32-61	D10303	10			D12133	2			YN231-YN260
0004	24		PK		22-4	23-32-61	D10303	6			D12133	8			YL951-YL999
0004	24		PK		17-9	23-32-61	D10303	6			D12133	8			YN231-YN260
0005	22		PA		21-8	23-32-61	D10303	9			SM00001		S		YL951-YL999

WIRE LIST

D280A108

91-21-11

Section W3280

Page 2

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3289	286A3289			PSU LCD VIDEO MONITOR (STA 727E+3R TO 727I+5R) TO VDU IN TRAY 4(-800) (continued)											
0005	22		PA		17-1	23-32-61	D10303		9		SM00001		S		YN231-YN260
0006	20		PA		22-4	23-32-61	D10303		4		D12133	5			YL951-YL999
0006	20		PA		17-9	23-32-61	D10303		4		D12133	5			YN231-YN260
0007	22		PA		1-3	23-32-61	D12133		3		SM00001		S		YL951-YN260
0008	22		PA		1-3	23-32-61	D12133		6		SM00001		S		YL951-YN260
0009	22		PA		1-3	23-32-61	D12133		7		SM00001		S		YL951-YN260
001CO				AA	0-0	23-32-61	D10303	= C1			D12135	= C1			YL951-YN260
001CX		0F		AA	21-10	23-32-61	D10303	= A1	5M		D12135	= A1			YL951-YL999
001CX		0F		AA	17-3	23-32-61	D10303	= A1	5M		D12135	= A1			YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W3280

Page 3 End

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3291	286A3291			PSU LCD VIDEO MONITOR (STA 727I+3L TO 800L) TO VDU IN TRAY 4(-800)											
0001	20	PA		13-5	23-32-62	D10309		1			D12139	1			YL951-YL999
0001	20	PA		16-1	23-32-62	D10309		1			D12139	1			YN231-YN260
0002	20	PA		13-5	23-32-62	D10309		2			D12139	4			YL951-YL999
0002	20	PA		16-1	23-32-62	D10309		2			D12139	4			YN231-YN260
0003	22	PA		13-5	23-32-62	D10309		10			D12139	2			YL951-YL999
0003	22	PA		16-1	23-32-62	D10309		10			D12139	2			YN231-YN260
0004	24	PK		13-5	23-32-62	D10309		6			D12139	8			YL951-YL999
0004	24	PK		16-1	23-32-62	D10309		6			D12139	8			YN231-YN260
0005	22	PA		12-9	23-32-62	D10309		9			SM00001		S		YL951-YL999
0005	22	PA		15-5	23-32-62	D10309		9			SM00001		S		YN231-YN260
0006	20	PA		13-5	23-32-62	D10309		4			D12139	5			YL951-YL999
0006	20	PA		16-1	23-32-62	D10309		4			D12139	5			YN231-YN260
0007	22	PA		1-2	23-32-62	D12139		3			SM00001		S		YL951-YL999
0007	22	PA		1-3	23-32-62	D12139		3			SM00001		S		YN231-YN260
0008	22	PA		1-2	23-32-62	D12139		6			SM00001		S		YL951-YL999
0008	22	PA		1-3	23-32-62	D12139		6			SM00001		S		YN231-YN260
0009	22	PA		1-2	23-32-62	D12139		7			SM00001		S		YL951-YL999
0009	22	PA		1-3	23-32-62	D12139		7			SM00001		S		YN231-YN260
001CO			AA	0-0	23-32-62	D10309		=C1			D12141	=C1			YL951-YN260
001CX		OF	AA	12-11	23-32-62	D10309		=A1	5M		D12141	=A1			YL951-YL999
001CX		OF	AA	15-7	23-32-62	D10309		=A1	5M		D12141	=A1			YN231-YN260
W3293	286A3293			PSU LCD VIDEO MONITOR (STA 727I+3R TO 800R) TO VDU IN TRAY 4(-800)											
0001	20	PA		19-5	23-32-62	D10311		1			D12145	1			YL951-YL999
0001	20	PA		21-3	23-32-62	D10311		1			D12145	1			YN231-YN260
0002	20	PA		19-5	23-32-62	D10311		2			D12145	4			YL951-YL999
0002	20	PA		21-3	23-32-62	D10311		2			D12145	4			YN231-YN260
0003	22	PA		19-5	23-32-62	D10311		10			D12145	2			YL951-YL999
0003	22	PA		21-3	23-32-62	D10311		10			D12145	2			YN231-YN260
0004	24	PK		19-5	23-32-62	D10311		6			D12145	8			YL951-YL999
0004	24	PK		21-3	23-32-62	D10311		6			D12145	8			YN231-YN260
0005	22	PA		18-9	23-32-62	D10311		9			SM00001		S		YL951-YL999
0005	22	PA		20-7	23-32-62	D10311		9			SM00001		S		YN231-YN260
0006	20	PA		19-5	23-32-62	D10311		4			D12145	5			YL951-YL999
0006	20	PA		21-3	23-32-62	D10311		4			D12145	5			YN231-YN260
0007	22	PA		1-2	23-32-62	D12145		3			SM00001		S		YL951-YL999
0007	22	PA		1-3	23-32-62	D12145		3			SM00001		S		YN231-YN260
0008	22	PA		1-2	23-32-62	D12145		6			SM00001		S		YL951-YL999
0008	22	PA		1-3	23-32-62	D12145		6			SM00001		S		YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W3290

Page 1

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W3293	286A3293				PSU LCD VIDEO MONITOR (STA 727I+3R TO 800R) TO VDU IN TRAY 4(-800) (continued)										
0009	22		PA		1-2	23-32-62	D12145	7			SM00001		S	YL951-YL999	
0009	22		PA		1-3	23-32-62	D12145	7			SM00001		S	YN231-YN260	
001CO				AA	0-0	23-32-62	D10311	=C1			D12147	=C1		YL951-YN260	
001CX			OF	AA	18-11	23-32-62	D10311	=A1	5M		D12147	=A1		YL951-YL999	
001CX			OF	AA	20-9	23-32-62	D10311	=A1	5M		D12147	=A1		YN231-YN260	
W3295	286A3295				PSU LCD VIDEO MONITOR (STA 790L TO STA 870L) TO VDU IN TRAY 4(-800)										
0001	20		PA		20-2	23-32-63	D10317	1			D12151	1		YL951-YL999	
0002	20		PA		20-2	23-32-63	D10317	2			D12151	4		YL951-YL999	
0003	22		PA		20-2	23-32-63	D10317	10			D12151	2		YL951-YL999	
0004	24		PK		20-2	23-32-63	D10317	6			D12151	8		YL951-YL999	
0005	22		PA		19-6	23-32-63	D10317	9			SM00001		S	YL951-YL999	
0006	20		PA		20-2	23-32-63	D10317	4			D12151	5		YL951-YL999	
0007	22		PA		1-2	23-32-63	D12151	3			SM00001		S	YL951-YL999	
0008	22		PA		1-2	23-32-63	D12151	6			SM00001		S	YL951-YL999	
0009	22		PA		1-2	23-32-63	D12151	7			SM00001		S	YL951-YL999	
001CO				AA	0-0	23-32-63	D10317	=C1			D12153	=C1		YL951-YL999	
001CX			OF	AA	19-8	23-32-63	D10317	=A1	5M		D12153	=A1		YL951-YL999	
W3297	286A3297				PSU LCD VIDEO MONITOR (STA 790R TO STA 870R) TO VDU IN TRAY 4(-800)										
0001	20		PA		26-0	23-32-63	D10319	1			D12157	1		YL951-YL999	
0002	20		PA		26-0	23-32-63	D10319	2			D12157	4		YL951-YL999	
0003	22		PA		26-0	23-32-63	D10319	10			D12157	2		YL951-YL999	
0004	24		PK		26-0	23-32-63	D10319	6			D12157	8		YL951-YL999	
0005	22		PA		25-4	23-32-63	D10319	9			SM00001		S	YL951-YL999	
0006	20		PA		26-0	23-32-63	D10319	4			D12157	5		YL951-YL999	
0007	22		PA		1-2	23-32-63	D12157	3			SM00001		S	YL951-YL999	
0008	22		PA		1-2	23-32-63	D12157	6			SM00001		S	YL951-YL999	
0009	22		PA		1-2	23-32-63	D12157	7			SM00001		S	YL951-YL999	
001CO				AA	0-0	23-32-63	D10319	=C1			D12159	=C1		YL951-YL999	
001CX			OF	AA	25-6	23-32-63	D10319	=A1	5M		D12159	=A1		YL951-YL999	

WIRE LIST

D280A108

91-21-11
Section W3290
Page 2 End
Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3307		286A3307				INPH, ELEX PNL AND FWD ATTD PNL										
0001		22		PA		31-9	23-31-06	D41337P		1		D48337P	B01			YC051-YC052
0001		22		PA		16-7	23-31-06	D41337P		1		D48337P	B01			YC053-YC055
0001		22		PA		16-2	23-31-06	D41337P		1		D48337P	B01			YC056-YD157
0001		22		PA		31-10	23-31-06	D41337P		1		D01507	24			YD158-YN260
0002		22		PA		31-10	23-31-06	D41337P		2		D01507	12			YD158-YN260
0003		22		PA		31-9	23-31-06	D41337P		3		D48337P	A06			YC051-YC052
0003		22		PA		16-7	23-31-06	D41337P		3		D48337P	A06			YC053-YC055
0003		22		PA		16-2	23-31-06	D41337P		3		D48337P	A06			YC056-YD157
0003		22		PA		31-10	23-31-06	D41337P		3		D01507	1			YD158-YN260
0004		20		PA		2-10	23-31-01	D10019		18		GD04168	DC..	1		YC051-YD157
0004		20		PA		1-9	23-31-01	D14366		2		SM00017		S		YN501-YR328
0005		24		PK		29-1	23-31-01	D10019		19		D41337P	12			YC051-YC055
0005		24		PK		29-3	23-31-01	D10019		19		D41337P	12			YC056-YD157
0005		24		PK		29-5	23-31-01	D10019		19		D41337P	12			YD158-YN260
0005		24		PK		29-5	23-31-01	D14366		19		D41337P	12			YN501-YR328
0006		22		PA		31-9	23-31-06	D41337P		6		D48337P	B06			YC051-YC052
0006		22		PA		16-7	23-31-06	D41337P		6		D48337P	B06			YC053-YC055
0006		22		PA		16-2	23-31-06	D41337P		6		D48337P	B06			YC056-YD157
0006		22		PA		31-10	23-31-06	D41337P		6		D01507	3			YD158-YN260
0007		22		PA		14-1	23-31-06	D41337P		13		TB1806Y	B001	1A		YD155-YN260
0007		22		PA		14-1	44-21-22	D41337P		13		TB1806Z	A009	1A		YN501-YR328
0008		24		PK		29-1	SPARE	D10019		40		D41337P	22			YC051-YC055
0008		24		PK		29-3	SPARE	D10019		40		D41337P	22			YC056-YD157
0008		24		PK		29-5	SPARE	D10019		40		D41337P	22			YD158-YN260
0008		24		PK		29-5	SPARE	D14366		40		D41337P	22			YN501-YR328
0009		20		PA		28-10	23-31-01	SM00003		9		D41337P	9			YC051-YC055
0009		20		PA		28-11	23-31-01	SM00003		9		D41337P	9			YC056-YC059
0009		20		PA		29-3	23-31-01	D10019		17		D41337P	9			YC060-YD157
0009		20		PA		29-5	23-31-01	D10019		17		D41337P	9			YD158-YN260
0009		20		PA		28-0	23-31-01	SM00015		S		D41337P	9			YN501-YR314
0009		20		PA		28-0	23-31-01	SM00015		9		D41337P	9			YR315-YR328
0011		20		PA		0-10	23-34-01	D10019		2		SM00003		9		YC051-YC059
0011		22		PA		29-3	23-34-01	D10019		2		D41337P	25			YC060-YD157
0011		20		PA		29-5	23-34-01	D10019		2		D41337P	27			YD158-YN260
0011		20		PA		29-5	44-21-10	D14366		11		D41337P	27			YN501-YR328
0012		22		PA		32-8	23-31-06	D48337P		A03		SP03891		S		YC051-YC052
0012		22		PA		32-10	23-31-06	D01507		20		SP03891		S		YD158-YN260
0013		22		PA		31-4	23-31-06	D48337P		A01		TB1806Y	B001	1A		YC051-YC052
0013		22		PA		16-2	23-31-06	D48337P		A01		TB1806Y	B001	1A		YC053-YC055

WIRE LIST

D280A108

91-21-11

Section W3300

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3307	286A3307				INPH, ELEX PNL AND FWD ATTD PNL (continued)											
0013	22		PA		15-10	23-31-06		D48337P	A01			TB1806Y	B001	1A		YC056-YD157
0013	22		PA		31-6	23-31-06		D01507		14		TB1806Y	B001	1A		YD158-YN260
0014	20		PA		6-0	23-31-06		D01507		21		GD04168	AC..	1		YD158-YN260
0015	20		PA		6-0	23-31-06		D01507		23		GD04168	ST..	1		YD158-YN260
0016	20		PA		6-0	23-31-06		D01507		5		GD04168	DC..	1		YD158-YN260
0017	20		PA		0-10	23-31-01		D10019		17		SM00003		9		YC051-YC059
0019	22		PA		29-1	23-42-12		D41337P		19		D10019		25		YC051-YC055
0019	22		PA		29-3	23-42-12		D41337P		19		D10019		25		YC056-YD157
0019	22		PA		29-5	23-42-12		D41337P		19		D10019		25		YD158-YN260
0020	20		PA		2-10	23-34-01		D10019		4		GD04168	DC..	1		YC051-YD157
0020	20		PA		3-1	23-34-01		D10019		4		GD04168	DC..	1		YD158-YN260
0020	20		PA		3-1	44-21-10		D14366		13		GD04168	DC..	1		YN501-YR328
0021	22		PA		29-1	23-34-01		D10019		3		D41337P		26		YC051-YC055
0021	22		PA		29-3	23-34-01		D10019		3		D41337P		26		YC056-YD157
0021	22		PA		29-5	23-34-01		D10019		3		D41337P		26		YD158-YN260
0021	20		PA		29-5	44-21-10		D14366		12		D41337P		26		YN501-YR328
0027	24		PK		31-10	23-31-06		D41337P		14		D01507	CAP	Y		YD158-YN260
0028	24		PK		31-10	23-31-06		D41337P		28		D01507		11		YD158-YD170
0028	24		PK		31-10	23-31-06		D41337P		28		D01507	CAP	Y		YL951-YN260
0067	22		PA		6-2	23-42-11		D10019		36		SP00595		9		YL951-YN260
0067	22		PA		0-7	23-42-11		SP00869		9		SP00595		9		YN501-YR315
0083	22		PA		26-11	23-42-14		SP00817		S		TB1806Z	A009	1A		YN501-YR328
0088	22		PA		17-1	44-21-22		D41337P		32		D45905P		19		YN501-YR328
0089	22		PA		17-1	44-21-22		D41337P		33		D45905P		20		YN501-YR328
0091	22		PA		17-1	44-21-26		D41337P		36		D45905P		24		YN501-YR328
0092	20		PA		17-1	44-21-26		D41337P		37		D45905P		23		YN501-YR328
0094	22		PA		7-8	23-31-01		SM00015		S		D13363		10		YN501-YR314
0094	22		PA		6-4	23-31-01		TB0954Y	B013	1A		D13363		10		YR315-YR328
0095	22		PA		7-8	23-31-01		SM00017		S		D13363		8		YN501-YR328
0096	22		PA		7-10	23-31-01		GD04164	ST..	1		D13363		5		YN501-YR328
0097	20		PA		1-11	23-31-01		SM00015		S		D14366		1		YN501-YR314
0097	20		PA		1-11	23-31-01		SM00015		9		D14366		1		YR315-YR328
0098	20		PA		1-9	23-31-01		SM00017		S		GD04168	DC..	1		YN501-YR328
0102	22		PA		17-1	44-21-22		D41337P		6		D45905P		2		YN501-YR328
0104	22		PA		3-6	23-31-01		SM00015		9		TB0954Y	A013	1A		YR315-YR328
0105	22		PA		0-7	23-31-01		TB0954Y	B013	1A		TB0954Y	B015	1A		YR315-YR328
0106	22		PA		17-1	44-21-22		D41337P		3		D45905P		6		YN501-YR328
0107	22		PA		28-8	23-42-12		D41337P		19		TB0954Y	A015	1A		YR315-YR328
0127	22		PA		17-1	44-21-22		D41337P		14		D45905P		21		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W3300

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3307		286A3307			INPH, ELEX PNL AND FWD ATTD PNL (continued)											
0128		22		PA		17-1	44-21-22	D41337P	28			D45905P	22			YN501-YR328
2001B		24		PL	AA	31-10	23-31-06	D41337P	5			D01507	17			YD158-YN260
2001R		24		PL	AA	0-0	23-31-06	D41337P	4			D01507	18			YD158-YN260
2002B		24		PL	AB	31-10	23-31-06	D41337P	8			D01507	7			YD158-YN260
2002R		24		PL	AB	0-0	23-31-06	D41337P	7			D01507	6			YD158-YN260
2003B		24		PL	EC	29-1	SPARE	D10019	39			D41337P	24			YC051-YC055
2003B		24		PL	EC	29-3	SPARE	D10019	39			D41337P	24			YC056-YD157
2003B		24		PL	AC	29-5	SPARE	D10019	39			D41337P	24			YD158-YN260
2003B		24		PL	AC	29-5	SPARE	D14366	39			D41337P	24			YN501-YR328
2003R		24		PL	EC	0-0	SPARE	D10019	38			D41337P	23			YC051-YD157
2003R		24		PL	AC	0-0	SPARE	D10019	38			D41337P	23			YD158-YN260
2003R		24		PL	AC	0-0	SPARE	D14366	38			D41337P	23			YN501-YR328
2011B		22		X2	EK	17-1	44-21-22	D41337P	8			D45905P	15			YN501-YR328
2011R		22		X2	EK	0-0	44-21-22	D41337P	7			D45905P	14			YN501-YR328
2011Z					EK	0-0	44-21-22	D41337P	DED			D45905P	PERB			YN501-YR313
2011Z					EK	0-0	44-21-22	D41337P				D45905P	PERB			YR314-YR317
2011Z					EK	0-0	44-21-22	D41337P			AA	D45905P			AD	YR318-YR328
2012B		22		X2	EL	17-1	44-21-22	D41337P	30			D45905P	8			YN501-YR328
2012R		22		X2	EL	0-0	44-21-22	D41337P	29			D45905P	7			YN501-YR328
2012Z					EL	0-0	44-21-22	D41337P	DED			D45905P	PERB			YN501-YR317
2012Z					EL	0-0	44-21-22	D41337P	DED			D45905P	DED			YR318-YR328
2014B		22		X2	EN	17-1	44-21-22	D41337P	5			D45905P	11			YN501-YR328
2014R		22		X2	EN	0-0	44-21-22	D41337P	4			D45905P	10			YN501-YR328
2014Z					EN	0-0	44-21-22	D41337P	DED			D45905P	PERB			YN501-YR313
2014Z					EN	0-0	44-21-22	D41337P			AA	D45905P	PERB			YR314-YR317
2014Z					EN	0-0	44-21-22	D41337P			AA	D45905P			AD	YR318-YR328
2501B		24		Y2	BA	29-1	23-31-01	D10019	21			D41337P	11			YC051-YC055
2501B		24		Y2	BA	29-3	23-31-01	D10019	21			D41337P	11			YC056-YD157
2501B		24		Y2	BA	29-5	23-31-01	D10019	21			D41337P	11			YD158-YN260
2501B		24		Y2	BA	29-5	23-31-01	D14366	21			D41337P	11			YN501-YR328
2501R		24		Y2	BA	0-0	23-31-01	D10019	20			D41337P	10			YC051-YN260
2501R		24		Y2	BA	0-0	23-31-01	D14366	20			D41337P	10			YN501-YR328
2501Z					BA	0-0	23-31-01	D10019	DED			D41337P	S/R			YC051-YD157
2501Z					BA	0-0	23-31-01	D10019	DED			D41337P			CA	YD158-YN260
2501Z					BA	0-0	23-31-01	D14366	DED			D41337P			CA	YN501-YR328
2502B		24		OT	AB	17-0	23-31-06	D41337P	28			D48337P	B02			YC051-YC052
2502B		24		OT	AB	16-7	23-31-06	D41337P	28			D48337P	B02			YC053-YC055
2502B		24		OT	AB	16-2	23-31-06	D41337P	28			D48337P	B02			YC056-YD157
2502W		24		OT	AB	0-0	23-31-06	D41337P	27			D48337P	A02			YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W3300

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W3307	286A3307			INPH, ELEX PNL AND FWD ATTD PNL (continued)												
2502Z				AB	0-0	23-31-06		D41337P	29			D48337P	PERG	IF		YC051-YC052
2502Z				AB	0-0	23-31-06		D41337P	29			D48337P	PERG	1F		YC053-YD157
2503B	24		Y6	AC	17-0	23-31-06		D41337P	5			D48337P	B04			YC051-YC052
2503B	24		Y6	AC	16-7	23-31-06		D41337P	5			D48337P	B04			YC053-YC055
2503B	24		Y6	AC	16-2	23-31-06		D41337P	5			D48337P	B04			YC056-YD157
2503R	24		Y6	AC	0-0	23-31-06		D41337P	4			D48337P	A04			YC051-YD157
2503Z				AC	0-0	23-31-06		D41337P	DED			D48337P	PERG	1F		YC051-YD157
2504B	24		Y6	AD	17-0	23-31-06		D41337P	8			D48337P	B05			YC051-YC052
2504B	24		Y6	AD	16-7	23-31-06		D41337P	8			D48337P	B05			YC053-YC055
2504B	24		Y6	AD	16-2	23-31-06		D41337P	8			D48337P	B05			YC056-YD157
2504R	24		Y6	AD	0-0	23-31-06		D41337P	7			D48337P	A05			YC051-YD157
2504Z				AD	0-0	23-31-06		D41337P	DED			D48337P	PERG	1F		YC051-YD157
2512B	22		X2	AL	17-1	44-21-22		D41337P	41			D45905P	17			YN501-YR328
2512R	22		X2	AL	0-0	44-21-22		D41337P	40			D45905P	16			YN501-YR328
2512Z				AL	0-0	44-21-22		D41337P	42			D45905P	18			YN501-YR313
2512Z				AL	0-0	44-21-22		D41337P			AA	D45905P	PERB			YR314-YR317
2512Z				AL	0-0	44-21-22		D41337P			AA	D45905P			AD	YR318-YR328
2523B	22		X2	AX	17-1	44-21-26		D41337P	39			D45905P	25			YN501-YR328
2523R	22		X2	AX	0-0	44-21-26		D41337P	38			D45905P	26			YN501-YR328
2523Z				AX	0-0	44-21-26		D41337P	DED			D45905P	PERB			YN501-YR328
3501B	24		Y3	CA	29-1	23-42-12		D41337P	17			D10019	14			YC051-YC055
3501B	24		Y3	CA	29-3	23-42-12		D41337P	17			D10019	14			YC056-YD157
3501B	24		Y3	CA	29-5	23-42-12		D41337P	17			D10019	14			YD158-YN260
3501B	24		Y3	CA	32-4	23-42-12		D41337P	17			D13363	13			YN501-YR328
3501R	24		Y3	CA	0-0	23-42-12		D41337P	16			D10019	16			YC051-YN260
3501R	24		Y3	CA	0-0	23-42-12		D41337P	16			D13363	7			YN501-YR328
3501Y	24		Y3	CA	0-0	23-42-12		D41337P	18			D10019	15			YC051-YN260
3501Y	24		Y3	CA	0-0	23-42-12		D41337P	18			D13363	6			YN501-YR328
3501Z				CA	0-0	23-42-12		D41337P	15			D10019	DED			YC051-YD157
3501Z				CA	0-0	23-42-12		D41337P			CA	D10019	DED			YD158-YN260
3501Z				CA	0-0	23-42-12		D41337P			CA	D13363	DED			YN501-YR328
3507B	24		Y3	HG	9-0	23-42-12		D14366	14			D13363	4			YN501-YR328
3507R	24		Y3	HG	0-0	23-42-12		D14366	16			D13363	2			YN501-YR328
3507Y	24		Y3	HG	0-0	23-42-12		D14366	15			D13363	3			YN501-YR328
3507Z				HG	0-0	23-42-12		D14366	DED			D13363	DED			YN501-YR328
FRAA					0-0	44-21-22		D41337P	42			D41337P			AA	YR314-YR328
FRAC					0-0	23-42-12		D41337P	15			D41337P			CA	YD158-YR328
FRAD					0-0	44-21-22		D45905P			AD	D45905P	18			YR318-YR328

WIRE LIST

D280A108

91-21-11

Section W3300

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice
W3309	286A3309				ATTENDANTS SPEAKERS/TWLU										
0001	22		PA		8-6	46-11-51	D12761		18			SP00619		9	YL951-YL954, YN231-YN235
0002	22		PA		3-7	46-11-51	D12761		19			GD03846	AC..	1	YL951-YL954, YN231-YN235
0003	22		PA		3-7	46-11-51	D12761		33			GD03846	ST..	1	YL951-YL954, YN231-YN235
0004	22		PA		3-7	46-11-51	D12761		39			GD03846	ST..	1	YL951-YL954, YN231-YN235
0005	24		PK		73-3	23-27-35	D44139P		A03			SP00827		9	YN501
0005	24		PK		93-0	23-27-35	D44139P		A03			SP00827		9	YR301-YR317
0006	24		PK		73-3	23-27-35	D44139P		B03			SP00829		9	YN501
0006	24		PK		93-0	23-27-35	D44139P		B03			SP00829		9	YR301-YR317
2001B	22		PB	AA	19-1	23-31-04	D44139P		B05			D40005P	2		YC051-YC055
2001B	22		PB	AA	19-6	23-31-04	D44139P		B05			D40005P	2		YC056-YR328
2001R	22		PB	AA	0-0	23-31-04	D44139P		A05			D40005P	1		ALL
2002B	22		PB	AB	98-1	23-31-04	D44139P		B06			SM00002		S	YC051-YC055
2002B	22		PB	AB	98-6	23-31-04	D44139P		B06			SM00002		S	YC056-YL999, YR301-YR328
2002B	22		PB	AB	79-1	23-31-04	D44139P		B06			SM00002		S	YN231-YN501
2002R	22		PB	AB	0-0	23-31-04	D44139P		A06			SM00001		S	ALL
2003B	22		PB	AC	6-10	23-31-04	SM00002			S		D40009P	2		YC051-YL999, YR301-YR328
2003B	22		PB	AC	6-0	23-31-04	SM00002			S		D40009P	2		YN231-YN501
2003R	22		PB	AC	0-0	23-31-04	SM00001			S		D40009P	1		ALL
2004B	22		PB	AD	4-5	23-31-04	SM00002			S		D40007P	2		YC051-YL999, YR301-YR328
2004B	22		PB	AD	3-8	23-31-04	SM00002			S		D40007P	2		YN231-YN501
2004R	22		PB	AD	0-0	23-31-04	SM00001			S		D40007P	1		ALL
2008B	22		X2	EH	27-0	46-11-51	D44139P		A08			D12761	14		YL951-YL954, YN231-YN235
2008R	22		X2	EH	0-0	46-11-51	D44139P		B08			D12761	20		YL951-YL954, YN231-YN235
2008Z				EH	0-0	46-11-51	D44139P		PERB			D12761	PERB		YL951-YL954, YN231-YN235
2009B	22		X2	EI	27-0	46-11-51	D44139P		A09			D12761	21		YL951-YL954, YN231-YN235
2009R	22		X2	EI	0-0	46-11-51	D44139P		B09			D12761	26		YL951-YL954, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W3300

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W3309	286A3309			ATTENDANTS SPEAKERS/TWLU (continued)												
2009Z				EI	0-0	46-11-51	D44139P	PERB				D12761	PERB			YL951-YL954, YN231-YN235
2010B	22	X2		EJ	27-0	46-11-51	D44139P	A10				D12761	34			YL951-YL954, YN231-YN235
2010R	22	X2		EJ	0-0	46-11-51	D44139P	B10				D12761	35			YL951-YL954, YN231-YN235
2010Z				EJ	0-0	46-11-51	D44139P	PERB				D12761	PERB			YL951-YL954, YN231-YN235
2505B	24	Y2		AZ	93-0	23-27-35	D44139P	B03				SP00829		V		YR318-YR328
2505R	24	Y2		AZ	0-0	23-27-35	D44139P	A03				SP00827		V		YR318-YR328
2505Z				AZ	0-0	23-27-35	D44139P	PERG	1F			SP00827	REF		AB	YR318-YR328
4001B	24	FS		KA	27-0	46-11-51	D44139P	A01				D12761	9			YL951-YL954, YN231-YN235
4001G	24	FS		KA	0-0	46-11-51	D44139P	A02				D12761	25			YL951-YL954, YN231-YN235
4001R	24	FS		KA	0-0	46-11-51	D44139P	B02				D12761	23			YL951-YL954, YN231-YN235
4001Y	24	FS		KA	0-0	46-11-51	D44139P	B01				D12761	24			YL951-YL954, YN231-YN235
4001Z				KA	0-0	46-11-51	D44139P	PERB				D12761	PERB			YL951-YL954, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W3300

Page 6 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		Diagram	From			To			Effectivity			
	Wire No.	GA	CO TY		Equip	Term		Type	Splice	Equip	Term	Type	Splice				
I	W3311	286A3311				AFT ATTENDANTS HANDSET (P14)											
I	0001	22	PA		109-0	23-42-12	D04181P		1			D10021	25			YC051-YL999	
I	0001	22	PA		89-9	23-42-12	D04181P		1			D10021	25			YN231-YN260	
I	0002	24	PK		109-0	23-31-01	D04181P		6			D10021	19			YC051-YL999	
	0002	24	PK		89-9	23-31-01	D04181P		6			D10021	19			YN231-YN260	
	0002	24	PK		89-9	23-31-01	D04181P		6			D14374	19			YN501	
I	0002	24	PK		109-0	23-31-01	D04181P		6			D14374	19			YR301-YR328	
I	0003	20	PA		109-0	23-31-01	D04181P		10			D10021	17			YC051-YL999	
	0003	20	PA		89-9	23-31-01	D04181P		10			D10021	17			YN231-YN260	
	0003	20	PA		86-2	23-31-01	D04181P		10			D40709P	A			YN501	
	0003	20	PA		105-6	23-31-01	D04181P		10			D40709P	A			YR301-YR307	
I	0003	20	PA		106-11	23-31-01	D04181P		10			SM00011		9		YR308-YR328	
I	0004	20	PA		3-11	23-31-01	GD03948		DC..	1		D10021	18			YC051-YD157	
	0004	20	PA		5-2	23-31-01	GD03948		DC..	1		D40709P	B			YN501-YR307	
I	0004	20	PA		3-2	23-31-01	GD03948		DC..	1		SM00013		9		YR308-YR328	
	0005	20	PA		8-0	23-42-12	GD11098		ST..	1		D10021			AC	YL951-YL999	
I	0005	20	PA		3-11	23-42-12	GD03948		ST..	1		D14374			AC	YR301-YR328	
	0006	22	PA		11-11	23-42-12	D11173		4			D10021	29			YL951-YL999	
I	0006	22	PA		11-11	23-42-12	D11173		4			D14374	29			YR301-YR328	
	0007	22	PA		11-11	23-42-12	D11173		5			D10021	30			YL951-YL999	
I	0007	22	PA		11-11	23-42-12	D11173		5			D14374	30			YR301-YR328	
	0022	24	PK		109-0	23-31-01	D04181P		9			D10021	22			YL951-YL999	
I	0022	24	PK		109-0	23-31-01	D04181P		9			D14374	22			YR301-YR328	
	0034	20	PA		3-6	23-31-01	D14374		1			D40711J	A			YN501-YR307	
I	0034	20	PA		3-10	23-31-01	D14374		1			SM00011		9		YR308-YR328	
	0035	20	PA		3-2	23-31-01	D14374		2			D40711J	B			YN501-YR307	
I	0035	20	PA		2-2	23-31-01	D14374		2			SM00013		9		YR308-YR328	
	0036	20	PA		2-4	23-31-01	D40709J		A			SM00011		9		YN501-YR307	
	0037	20	PA		2-0	23-31-01	D40709J		B			SM00006		9		YN501-YR307	
	0038	20	PA		1-9	23-31-01	D40711P		A			SM00011		9		YN501-YR307	
	0039	20	PA		1-6	23-31-01	D40711P		B			SM00006		9		YN501-YR307	
	0044	22	PA		2-10	23-31-01	D11815		8			SM00006		9		YN501-YR307	
I	0044	22	PA		4-5	23-31-01	D11815		8			SM00013		9		YR308-YR328	
	0045	22	PA		4-7	23-31-01	D11815		5			D40709J	C			YN501-YR307	
I	0045	22	PA		7-7	23-31-01	D11815		5			GD03951	ST..	1		YR308-YR328	
	0046	22	PA		2-10	23-31-01	D11815		10			SM00011		9		YN501-YR314	
I	0046	22	PA		8-1	23-31-01	D11815		10			TB0952Y	B013	1A		YR315-YR328	
	0047	20	PA		6-6	23-31-01	D40709P		C			GD03951	ST..	1		YN501-YR307	
I	0053	22	PA		5-4	23-31-01	SM00011			9		TB0952Y	A013	1A		YR315-YR328	
I	0054	22	PA		0-7	23-31-01	TB0952Y		B013	1A		TB0952Y	B015	1A		YR315-YR328	

WIRE LIST

D280A108

91-21-11

Section W3310

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To				
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3311		286A3311				AFT ATTENDANTS HANDSET (P14) (continued)									
	0055	22	PA		110-6	23-42-12	D04181P				TB0952Y	A015	1A		YR315-YR328
	2001B	24	Y2	AB	109-0	23-31-01	D04181P				D10021	21			YC051-YL999
	2001B	24	Y2	AB	89-9	23-31-01	D04181P				D10021	21			YN231-YN260
	2001B	24	Y2	AB	89-9	23-31-01	D04181P				D14374	21			YN501
	2001B	24	Y2	AB	109-0	23-31-01	D04181P				D14374	21			YR301-YR328
	2001R	24	Y2	AB	0-0	23-31-01	D04181P				D10021	20			YC051-YN260
	2001R	24	Y2	AB	0-0	23-31-01	D04181P				D14374	20			YN501-YR328
	2001Z			AB	0-0	23-31-01	D04181P			AA	D10021	DED			YC051-YN260
	2001Z			AB	0-0	23-31-01	D04181P			AA	D14374	DED			YN501-YR328
	2003B	24	Y2	EC	109-0	23-31-01	D04181P				D10021	24			YL951-YL999
	2003B	24	Y2	EC	109-0	23-31-01	D04181P				D14374	24			YR301-YR328
	2003R	24	Y2	EC	0-0	23-31-01	D04181P				D10021	23			YL951-YL999
	2003R	24	Y2	EC	0-0	23-31-01	D04181P				D14374	23			YR301-YR328
	2003Z			EC	0-0	23-31-01	D04181P			AA	D10021	DED			YL951-YL999
	2003Z			EC	0-0	23-31-01	D04181P			AA	D14374	DED			YR301-YR328
	3501B	24	Y3	AA	109-0	23-42-12	D04181P				D10021	14			YC051-YL999
	3501B	24	Y3	AA	89-9	23-42-12	D04181P				D10021	14			YN231-YN260
	3501B	24	Y3	HA	86-2	23-42-12	D04181P				D40669J	A			YN501
	3501B	24	Y3	HA	105-5	23-42-12	D04181P				D40669J	A			YR301-YR307
	3501B	24	Y3	HA	109-2	23-42-12	D04181P				D11815	13			YR308-YR328
	3501R	24	Y3	AA	0-0	23-42-12	D04181P				D10021	16			YC051-YN260
	3501R	24	Y3	HA	0-0	23-42-12	D04181P				D40669J	B			YN501-YR307
	3501R	24	Y3	HA	0-0	23-42-12	D04181P				D11815	7			YR308-YR328
	3501Y	24	Y3	AA	0-0	23-42-12	D04181P				D10021	15			YC051-YN260
	3501Y	24	Y3	HA	0-0	23-42-12	D04181P				D40669J	C			YN501-YR307
	3501Y	24	Y3	HA	0-0	23-42-12	D04181P				D11815	6			YR308-YR328
	3501Z			AA	0-0	23-42-12	D04181P			AA	D10021	DED			YC051-YN260
	3501Z			HA	0-0	23-42-12	D04181P			AA	D40669J	DED			YN501-YR307
	3501Z			HA	0-0	23-42-12	D04181P			AA	D11815	DED			YR308-YR328
	3502B	24	Y3	AC	11-11	23-42-12	D11173				D10021	28			YL951-YL999
	3502B	24	Y3	AC	11-11	23-42-12	D11173				D14374	28			YR301-YR328
	3502R	24	Y3	AC	0-0	23-42-12	D11173				D10021	26			YL951-YL999
	3502R	24	Y3	AC	0-0	23-42-12	D11173				D14374	26			YR301-YR328
	3502Y	24	Y3	AC	0-0	23-42-12	D11173				D10021	27			YL951-YL999
	3502Y	24	Y3	AC	0-0	23-42-12	D11173				D14374	27			YR301-YR328
	3502Z			AC	0-0	23-42-12	D11173				D10021			AC	YL951-YL999
	3502Z			AC	0-0	23-42-12	D11173				D14374			AC	YR301-YR328
	3510B	24	Y3	HJ	3-6	23-42-12	D14374				D40697P	A			YN501-YR307
	3510B	24	Y3	HJ	6-7	23-42-12	D14374				D11815	4			YR308-YR328

WIRE LIST

D280A108

91-21-11

Section W3310

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3311		286A3311			AFT ATTENDANTS HANDSET (P14) (continued)											
3510R		24		Y3	HJ	0-0	23-42-12	D14374		16		D40697P		B		YN501-YR307
3510R		24		Y3	HJ	0-0	23-42-12	D14374		16		D11815		2		YR308-YR328
3510Y		24		Y3	HJ	0-0	23-42-12	D14374		15		D40697P		C		YN501-YR307
3510Y		24		Y3	HJ	0-0	23-42-12	D14374		15		D11815		3		YR308-YR328
3510Z					HJ	0-0	23-42-12	D14374		DED		D40697P		DED		YN501-YR307
3510Z					HJ	0-0	23-42-12	D14374		DED		D11815		DED		YR308-YR328
3511B		24		PM	HK	4-7	23-42-12	D11815		13		D40669P		A		YN501-YR307
3511R		24		PM	HK	0-0	23-42-12	D11815		7		D40669P		B		YN501-YR307
3511Y		24		PM	HK	0-0	23-42-12	D11815		6		D40669P		C		YN501-YR307
3513B		24		PM	HM	4-0	23-42-12	D11815		4		D40697J		A		YN501-YR307
3513R		24		PM	HM	0-0	23-42-12	D11815		2		D40697J		B		YN501-YR307
3513Y		24		PM	HM	0-0	23-42-12	D11815		3		D40697J		C		YN501-YR307
FRAA						0-0	23-42-12	D04181P		5		D04181P			AA	ALL
W3319		286A3319			F/O AUDIO SEL PNL TO INPH											
0001		22		PA		25-10	23-51-21	D04331P		A02		D00137		C		YC051-YC055
0001		22		PA		26-5	23-51-21	D04331P		A02		D00137		C		YC056-YD158, YL951-YR328
0002		22		PA		25-10	23-51-21	D04331P		A03		D00137		D		YC051-YC055
0002		22		PA		26-5	23-51-21	D04331P		A03		D00137		D		YC056-YD158, YL951-YR328
0003		22		PA		25-10	23-51-21	D04331P		B03		D00137		V		YC051-YC055
0003		22		PA		26-5	23-51-21	D04331P		B03		D00137		V		YC056-YD158, YL951-YR328
0004		22		PA		25-10	23-51-21	D04331P		A04		D00137		T		YC051-YC055
0004		22		PA		26-5	23-51-21	D04331P		A04		D00137		T		YC056-YD158, YL951-YR328
0005		22		PA		3-5	23-51-21	GD00809		DC.. 1A		D00137		P		YC051-YD158, YL951-YR328
0007		20		CQ		3-4	33-11-33	D00137		K		TB0801W		A005 1		YC051-YC053
0007		20		CQ		3-5	33-11-33	D00137		K		TB0801W		A005 1		YC054-YD157
0007		20		PA		3-5	33-11-33	D00137		K		TB0801W		A005 1		YD158, YL951-YR328
0008		20		CQ		3-5	33-18-62	D00137		N		TB0801X		A003 1A		YC051-YD157
0008		20		CQ		3-8	33-18-62	D00137		N		TB0804Y		B005 1A		YD158, YL951-YR328
0009		20		CQ		3-1	33-11-33	D00137		L		GD00805		AC.. 1A		YC051-YD157
0009		20		PA		3-1	33-11-33	D00137		L		GD00805		AC.. 1A		YD158, YL951-YR328
0010		24		PK		25-10	23-43-11	D00135		7		D04331P		B14		YC051-YC055
0010		24		PK		26-5	23-43-11	D00135		7		D04331P		B14		YC056-YD157

WIRE LIST

D280A108

91-21-11

Section W3310

Page 3

Nov 12/2012



WIRE LIST
D280A108

91-21-11
Section W3310
Page 4
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W3319	286A3319	F/O AUDIO SEL PNL TO INPH (continued)													
2001R	24	PL	AD	0-0	23-51-21	D04331P	A10		D00129	1				YC051-YD158, YL951-YR328	
2501B	24	Y2	AA	25-10	23-51-21	D04331P	B01		D00137	B				YC051-YC055	
2501B	24	Y2	AA	26-5	23-51-21	D04331P	B01		D00137	B				YC056-YD158, YL951-YR328	
2501R	24	Y2	AA	0-0	23-51-21	D04331P	A01		D00137	A				YC051-YD158, YL951-YR328	
2501Z			AA	0-0	23-51-21	D04331P	B02		D00137			FA		YC051-YD157	
2501Z			AA	0-0	23-51-21	D04331P	PERG	1F	D00137			FA		YD158, YL951-YR328	
2502B	24	Y2	AB	32-2	23-51-21	D04331P	B06		SM00002		S			YC051-YC055	
2502B	24	Y2	AB	32-9	23-51-21	D04331P	B06		SM00002		S			YC056-YD157	
2502B	24	Y2	AB	32-9	23-51-21	D04331P	B06		SM00002		9			YD158, YL951-YR328	
2502R	24	Y2	AB	0-0	23-51-21	D04331P	A06		SM00001		S			YC051-YD157	
2502R	24	Y2	AB	0-0	23-51-21	D04331P	A06		SM00001		9			YD158, YL951-YR328	
2502Z			AB	0-0	23-51-21	D04331P	PERG	1F	SM00001	DED				YC051-YD158, YL951-YR328	
2503B	24	Y2	AC	24-2	23-51-21	D04331P	B07		D06051	B				YC051-YC055	
2503B	24	Y2	AC	24-9	23-51-21	D04331P	B07		D06051	B				YC056-YD158, YL951-YR328	
2503R	24	Y2	AC	0-0	23-51-21	D04331P	A07		D06051	A				YC051-YD158, YL951-YR328	
2503Z			AC	0-0	23-51-21	D04331P	PERG	1F	D06051	C				YC051-YD157	
2503Z			AC	0-0	23-51-21	D04331P	A09		D06051	C				YD158, YL951-YR328	
3001B	24	PM	AG	13-0	23-51-21	D00137	U		TB0805X	B002	1A			YC051-YD158	
3001B	24	PM	AG	13-0	23-51-21	D00137	U		TB0805Y	B011	1A			YL951-YR328	
3001R	24	PM	AG	0-0	23-51-21	D00137	S		TB0805X	A003	1A			YC051-YD158	
3001R	24	PM	AG	0-0	23-51-21	D00137	S		TB0805Y	A011	1A			YL951-YR328	
3001Y	24	PM	AG	0-0	23-51-21	D00137	R		TB0805X	A002	1A			YC051-YD158, YL951-YR328	
3501B	24	Y3	AE	23-10	23-51-21	D04331P	B08		SM00008		S			YC051-YC055	
3501B	24	Y3	AE	24-4	23-51-21	D04331P	B08		SM00008		S			YC056-YD157	
3501B	24	Y3	AE	24-4	23-51-21	D04331P	B08		SM00008		9			YD158, YL951-YR328	
3501R	24	Y3	AE	0-0	23-51-21	D04331P	A08		SM00007		S			YC051-YD157	
3501R	24	Y3	AE	0-0	23-51-21	D04331P	A08		SM00007		9			YD158, YL951-YR328	
3501Y	24	Y3	AE	0-0	23-51-21	D04331P	B09		SM00006		S			YC051-YD157	
3501Y	24	Y3	AE	0-0	23-51-21	D04331P	B09		SM00006		9			YD158, YL951-YR328	
3501Z			AE	0-0	23-51-21	D04331P	PERG	1F	SM00006	DED				YC051-YD157	
3501Z			AE	0-0	23-51-21	D04331P	B11		SM00006	DED				YD158, YL951-YR328	
3502B	24	Y3	AF	32-2	23-51-21	D04331P	A05		SM00005		S			YC051-YC055	

WIRE LIST

D280A108

91-21-11

Section W3310

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3319		286A3319			F/O AUDIO SEL PNL TO INPH (continued)											
3502B		24		Y3	AF	32-9	23-51-21	D04331P	A05			SM00005		S		YC056-YD157
3502B		24		Y3	AF	32-9	23-51-21	D04331P	A05			SM00005		9		YD158, YL951-YR328
3502R		24		Y3	AF	0-0	23-51-21	D04331P	B04			SM00004		S		YC051-YD157
3502R		24		Y3	AF	0-0	23-51-21	D04331P	B04			SM00004		9		YD158, YL951-YR328
3502Y		24		Y3	AF	0-0	23-51-21	D04331P	B05			SM00003		S		YC051-YD157
3502Y		24		Y3	AF	0-0	23-51-21	D04331P	B05			SM00003		9		YD158, YL951-YR328
3502Z					AF	0-0	23-51-21	D04331P	PERG	1F		SM00003	DED			YC051-YD157
3502Z					AF	0-0	23-51-21	D04331P	B02			SM00003	DED			YD158, YL951-YR328
A-AA					VA	0-0	23-51-21	D06033	BLU			SM00001		S		YC051-YD157
A-AA					VA	0-0	23-51-21	D06033	BLU			SM00001		9		YD158, YL951-YR328
A-AB					VA	0-0	23-51-21	D06033	BLK			SM00002		S		YC051-YD157
A-AB					VA	0-0	23-51-21	D06033	BLK			SM00002		9		YD158, YL951-YR328
C-CA					VC	0-0	23-51-21	D06029	RED			SM00004		S		YC051-YD157
C-CA					VC	0-0	23-51-21	D06029	RED			SM00004		9		YD158, YL951-YR328
C-CB					VC	0-0	23-51-21	D06029	BLK			SM00005		S		YC051-YD157
C-CB					VC	0-0	23-51-21	D06029	BLK			SM00005		9		YD158, YL951-YR328
C-CC					VC	0-0	23-51-21	D06029	BLU			SM00003		S		YC051-YD157
C-CC					VC	0-0	23-51-21	D06029	BLU			SM00003		9		YD158, YL951-YR328
D-DA					VD	0-0	23-51-21	D06043	RED			SM00007		S		YC051-YD157
D-DA					VD	0-0	23-51-21	D06043	RED			SM00007		9		YD158, YL951-YR328
D-DB					VD	0-0	23-51-21	D06043	BLK			SM00008		S		YC051-YD157
D-DB					VD	0-0	23-51-21	D06043	BLK			SM00008		9		YD158, YL951-YR328
D-DC					VD	0-0	23-51-21	D06043	BLU			SM00006		S		YC051-YD157
D-DC					VD	0-0	23-51-21	D06043	BLU			SM00006		9		YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W3310

Page 6 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3323		286A3323					CAPT AUDIO SEL PNL TO INPH									
0001		22		PA		31-7	23-51-11	D04155P	A02			D00133	C			YC051-YC055
0001		22		PA		31-9	23-51-11	D04155P	A02			D00133	C			YC056-YR328
0002		22		PA		31-7	23-51-11	D04155P	A03			D00133	D			YC051-YC055
0002		22		PA		31-9	23-51-11	D04155P	A03			D00133	D			YC056-YR328
0003		22		PA		31-7	23-51-11	D04155P	B03			D00133	V			YC051-YC055
0003		22		PA		31-9	23-51-11	D04155P	B03			D00133	V			YC056-YR328
0004		22		PA		31-7	23-51-11	D04155P	A04			D00133	T			YC051-YC055
0004		22		PA		31-9	23-51-11	D04155P	A04			D00133	T			YC056-YR328
0005		22		PA		3-7	23-51-11	D00133	P			GD00803	DC..	1A		ALL
0007		20		CQ		4-1	33-11-33	D00133	K			TB0801W	B021	1		YC051-YD157, YN231-YR328
0007		20		PA		4-1	33-11-33	D00133	K			TB0801W	B021	1		YD158-YL999
0008		20		CQ		3-9	33-18-62	D00133	N			TB0801X	B002	1A		YC051-YC052
0008		20		CQ		4-1	33-18-62	D00133	N			TB0804Y	A007	1A		YC053-YR328
0009		20		CQ		3-8	33-11-33	D00133	L			GD00805	AC..	1A		YC051-YD157, YN231-YR328
0009		20		PA		3-8	33-11-33	D00133	L			GD00805	AC..	1A		YD158-YL999
0011		20		PA		3-7	23-51-11	GD00803	ST..	1A		D00133			FA	ALL
0014		22		PA		31-7	23-51-11	D04155P	A13			D00133	E			YC051-YC055
0014		22		PA		31-9	23-51-11	D04155P	A13			D00133	E			YC056-YD157
0015		22		PA		34-6	23-51-11	D04155P	B13			D06049	E			YC051-YC055
0015		22		PA		34-8	23-51-11	D04155P	B13			D06049	E			YC056-YD157
0016		20		PA		3-8	23-51-11	D06049	F			GD02303	DC..	E		YC051-YD157
0017		24		B6		32-1	23-22-11	D00131	1			D04155P	A15			YC051-YC055
0017		24		B6		32-3	23-22-11	D00131	1			D04155P	A15			YC056-YD157
0018		24		B6		32-1	23-22-11	D00131	2			D04155P	A16			YC051-YC055
0018		24		B6		32-3	23-22-11	D00131	2			D04155P	A16			YC056-YD157
0019		24		B6		32-1	23-22-11	D00131	3			D04155P	A17			YC051-YC055
0019		24		B6		32-3	23-22-11	D00131	3			D04155P	A17			YC056-YD157
0020		24		B6		32-1	23-22-11	D00131	4			D04155P	A18			YC051-YC055
0020		24		B6		32-3	23-22-11	D00131	4			D04155P	A18			YC056-YD157
0021		22		CQ		31-4	23-27-11	D00131	CAP	Y		D04155P	CAP	Y		YC051-YC053
0021		22		CQ		31-4	23-27-11	D00131	13			D04155P	A20			YC054-YC055
0021		22		CQ		32-3	23-27-11	D00131	13			D04155P	A20			YC056-YD157
0022		24		PK		32-1	23-43-11	D00131	7			D04155P	B15			YC051-YC055
0022		24		PK		32-3	23-43-11	D00131	7			D04155P	B15			YC056-YD157
0030		22		PA		0-7	23-51-11	D00133	F			D00133	G			ALL
0032		20		CQ		4-4	33-18-62	D00131	15			TB0803Z	B005	1A		YC051-YC052, YC070-YD157

WIRE LIST

D280A108

91-21-11

Section W3320

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W3323	286A3323				CAPT AUDIO SEL PNL TO INPH (continued)												
0032	20		CQ		5-0	33-18-62		D00131	15			TB0804Z	B021	1A		YC054-YC064, YC067-YC068	
0032	20		CQ		5-0	33-18-62		D00131	15			TB0803Z	B05	1A		YC065	
0033	24		PK		32-1	23-15-15		D00131	19			D04155P	B17			YC051-YC055	
0033	24		PK		32-3	23-15-15		D00131	19			D04155P	B17			YC056-YD157	
0034	24		PK		32-1	23-15-15		D00131	20			D04155P	B20			YC051-YC055	
0034	24		PK		32-3	23-15-15		D00131	20			D04155P	B20			YC056-YD157	
0035	24		PK		32-1	23-15-15		D00131	10			D04155P	A14			YC051-YC055	
0035	24		PK		32-3	23-15-15		D00131	10			D04155P	A14			YC056-YD157	
0036	24		PK		32-1	23-15-15		D00131	14			D04155P	B14			YC051-YC055	
0036	24		PK		32-3	23-15-15		D00131	14			D04155P	B14			YC056-YD157	
0037	22		PA		4-3	23-15-15		D00131	18			GD00805	DC..	1A		YC051-YD157	
0038	20		CQ		3-10	33-18-62		D00133	M			TB0803Z	B005	1A		YD158-YR328	
0055	24		PK		32-1	23-27-31		D04155P	B14			SP00087		S		YD158-YR328	
0058	24		PK		0-7	23-27-31		SP00083		S		SP00087		S		YL951-YR328	
0059	24		PK		0-7	23-27-31		SP00081		S		SP00083		S		YL951-YR328	
2001B	24		PL	AD	41-9	23-51-11		D04155P	B10			D00127	2			YC051-YC052	
2001B	24		PL	AD	41-6	23-51-11		D04155P	B10			D00127	2			YC053-YC055	
2001B	24		PL	AD	41-8	23-51-11		D04155P	B10			D00127	2			YC056-YD151	
2001B	24		PL	AD	38-10	23-51-11		D04155P	B10			D00127	2			YD152-YL956, YN231-YN235, YN501	
2001B	24		PL	AD	39-3	23-51-11		D04155P	B10			D00127	2			YL957-YL999, YN236-YN260, YR301-YR328	
2001R	24		PL	AD	0-0	23-51-11		D04155P	A10			D00127	1			ALL	
2501B	24		Y2	AA	31-7	23-51-11		D04155P	B01			D00133	B			YC051-YC055	
2501B	24		Y2	AA	31-9	23-51-11		D04155P	B01			D00133	B			YC056-YR328	
2501R	24		Y2	AA	0-0	23-51-11		D04155P	A01			D00133	A			ALL	
2501Z				AA	0-0	23-51-11		D04155P	B02			D00133				YC051-YD157	
2501Z				AA	0-0	23-51-11		D04155P	PERG	1F		D00133			FA FA	YD158-YR328	
2502B	24		Y2	AB	38-2	23-51-11		D04155P	B06			SM00002		S		YC051-YC052	
2502B	24		Y2	AB	37-11	23-51-11		D04155P	B06			SM00002		S		YC053-YC055	
2502B	24		Y2	AB	38-1	23-51-11		D04155P	B06			SM00002		S		YC056-YD157	
2502B	24		Y2	AB	38-1	23-51-11		D04155P	B06			SM00002		9		YD158-YL956, YN231-YN235, YN501	
2502B	24		Y2	AB	38-5	23-51-11		D04155P	B06			SM00002		9		YL957-YL999, YN236-YN260, YR301-YR328	
2502R	24		Y2	AB	0-0	23-51-11		D04155P	A06			SM00001		S		YC051-YD157	

WIRE LIST

D280A108

91-21-11

Section W3320

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W3323	286A3323	CAPT AUDIO SEL PNL TO INPH (continued)			
2502R	24	Y2 AB	0-0 23-51-11 D04155P A06	SM00001 9	YD158-YR328
2502Z		AB	0-0 23-51-11 D04155P PERG 1F	SM00001 DED	YC051-YL999
2502Z		AB	0-0 23-51-11 D04155P PERG 1F	SM00002 DED	YN231-YR328
2503B	24	Y2 AC	34-6 23-51-11 D04155P B07	D06049 B	YC051-YC055
2503B	24	Y2 AC	34-8 23-51-11 D04155P B07	D06049 B	YC056-YR328
2503R	24	Y2 AC	0-0 23-51-11 D04155P A07	D06049 A	ALL
2503Z		AC	0-0 23-51-11 D04155P PERG 1F	D06049 C	YC051-YD157
2503Z		AC	0-0 23-51-11 D04155P A09	D06049 C	YD158-YR328
2504B	24	M5 AH	26-3 34-41-11 D04155P B11	TB1808X B001 1A	YC051-YC055
2504B	24	M5 AH	26-5 34-41-11 D04155P B11	TB1808X B001 1A	YC056-YR328
2504R	24	M5 AH	0-0 34-41-11 D04155P A11	TB1808X A001 1A	ALL
2504ZI		AH	0-0 34-41-11 D04155P B12	TB1808X A002 1A	ALL
2504ZO		AH	0-0 34-41-11 D04155P PERG 1F	GB01808 ST.. 1A	ALL
3001B	24	PM AG	7-0 23-51-11 D00133 U	TB0806X B002 1A	YC051-YD170
3001B	24	PM AG	7-0 23-51-11 D00133 U	TB0806Y A003 1A	YL951-YR328
3001R	24	PM AG	0-0 23-51-11 D00133 S	TB0806X A003 1A	YC051-YD170
3001R	24	PM AG	0-0 23-51-11 D00133 S	TB0806Y B001 1A	YL951-YR328
3001Y	24	PM AG	0-0 23-51-11 D00133 R	TB0806X A002 1A	YC051-YD170
3001Y	24	PM AG	0-0 23-51-11 D00133 R	TB0806Y A001 1A	YL951-YR328
3501B	24	Y3 AE	34-3 23-51-11 D04155P B08	SM00008 S	YC051-YC055
3501B	24	Y3 AE	34-5 23-51-11 D04155P B08	SM00008 S	YC056-YD157
3501B	24	Y3 AE	34-5 23-51-11 D04155P B08	SM00008 9	YD158-YR328
3501R	24	Y3 AE	0-0 23-51-11 D04155P A08	SM00007 S	YC051-YD157
3501R	24	Y3 AE	0-0 23-51-11 D04155P A08	SM00007 9	YD158-YR328
3501Y	24	Y3 AE	0-0 23-51-11 D04155P B09	SM00006 S	YC051-YD157
3501Y	24	Y3 AE	0-0 23-51-11 D04155P B09	SM00006 9	YD158-YR328
3501Z		AE	0-0 23-51-11 D04155P PERG 1F	SM00006 DED	YC051-YD157
3501Z		AE	0-0 23-51-11 D04155P A12	SM00006 DED	YD158-YR328
3502B	24	Y3 AF	38-1 23-51-11 D04155P A05	SM00005 S	YC051-YC052
3502B	24	Y3 AF	37-10 23-51-11 D04155P A05	SM00005 S	YC053-YC055
3502B	24	Y3 AF	38-0 23-51-11 D04155P A05	SM00005 S	YC056-YD157
3502B	24	Y3 AF	38-0 23-51-11 D04155P A05	SM00005 9	YD158-YL956, YN231-YN235, YN501
3502B	24	Y3 AF	38-4 23-51-11 D04155P A05	SM00005 9	YL957-YL999, YN236-YN260, YR301-YR328
3502R	24	Y3 AF	0-0 23-51-11 D04155P B04	SM00004 S	YC051-YD157
3502R	24	Y3 AF	0-0 23-51-11 D04155P B04	SM00004 9	YD158-YR328
3502Y	24	Y3 AF	0-0 23-51-11 D04155P B05	SM00003 S	YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W3320

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3323		286A3323			CAPT AUDIO SEL PNL TO INPH (continued)											
3502Y		24		Y3	AF	0-0	23-51-11	D04155P	B05			SM00003		9		YD158-YR328
3502Z					AF	0-0	23-51-11	D04155P	PERG	1F		SM00003	DED			YC051-YD157
3502Z					AF	0-0	23-51-11	D04155P	B02			SM00003	DED			YD158-YR328
A-AA					VA	0-0	23-51-11	D06031	BLU			SM00001		S		YC051-YD157
A-AA					VA	0-0	23-51-11	D06031	BLU			SM00001		9		YD158-YR328
A-AB					VA	0-0	23-51-11	D06031	BLK			SM00002		S		YC051-YD157
A-AB					VA	0-0	23-51-11	D06031	BLK			SM00002		9		YD158-YR328
C-CA					VC	0-0	23-51-11	D06041	RED			SM00007		S		YC051-YD157
C-CA					VC	0-0	23-51-11	D06041	RED			SM00007		9		YD158-YR328
C-CB					VC	0-0	23-51-11	D06041	BLK			SM00008		S		YC051-YD157
C-CB					VC	0-0	23-51-11	D06041	BLK			SM00008		9		YD158-YR328
C-CC					VC	0-0	23-51-11	D06041	BLU			SM00006		S		YC051-YD157
C-CC					VC	0-0	23-51-11	D06041	BLU			SM00006		9		YD158-YR328
D-DA					VD	0-0	23-51-11	D06027	RED			SM00004		S		YC051-YD157
D-DA					VD	0-0	23-51-11	D06027	RED			SM00004		9		YD158-YR328
D-DB					VD	0-0	23-51-11	D06027	BLK			SM00005		S		YC051-YD157
D-DB					VD	0-0	23-51-11	D06027	BLK			SM00005		9		YD158-YR328
D-DC					VD	0-0	23-51-11	D06027	BLU			SM00003		S		YC051-YD157
D-DC					VD	0-0	23-51-11	D06027	BLU			SM00003		9		YD158-YR328
W3327		286A3327			F/OBS FLIGHT INPH											
0001		22		PA		29-4	23-51-31	D04153P	A02			D00139	C			YC051-YC052
0001		22		PA		29-0	23-51-31	D04153P	A02			D00139	C			YC053-YC055
0001		22		PA		28-11	23-51-31	D04153P	A02			D00139	C			YC056-YC058
0001		22		PA		28-10	23-51-31	D04153P	A02			D00139	C			YC059-YD158, YL951-YR328
0002		22		PA		29-4	23-51-31	D04153P	A03			D00139	D			YC051-YC052
0002		22		PA		29-0	23-51-31	D04153P	A03			D00139	D			YC053-YC055
0002		22		PA		28-11	23-51-31	D04153P	A03			D00139	D			YC056-YC058
0002		22		PA		28-10	23-51-31	D04153P	A03			D00139	D			YC059-YD158, YL951-YR328
0003		22		PA		29-4	23-51-31	D04153P	B03			D00139	V			YC051-YC052
0003		22		PA		29-0	23-51-31	D04153P	B03			D00139	V			YC053-YC055
0003		22		PA		28-11	23-51-31	D04153P	B03			D00139	V			YC056-YC058
0003		22		PA		28-10	23-51-31	D04153P	B03			D00139	V			YC059-YD158, YL951-YR328
0004		22		PA		29-4	23-51-31	D04153P	A04			D00139	T			YC051-YC052
0004		22		PA		29-0	23-51-31	D04153P	A04			D00139	T			YC053-YC055
0004		22		PA		28-11	23-51-31	D04153P	A04			D00139	T			YC056-YC058

WIRE LIST

D280A108

91-21-11

Section W3320

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3327	286A3327				F/OBS FLIGHT INPH (continued)										
0004	22		PA		28-10	23-51-31	D04153P	A04			D00139	T			YC059-YD158, YL951-YR328
0005	22		PA		2-8	23-51-31	D00139	P			GD00508	DC..	1A		YC051-YC052
0005	22		PA		2-4	23-51-31	D00139	P			GD00508	DC..	1A		YC053-YD158, YL951-YR328
0007	20		CQ		2-9	33-12-12	D00139	K			TB0506Y	A011	1A		YC051-YC052
0007	20		CQ		2-11	33-12-12	D00139	K			TB0506Y	A011	1A		YC053-YC058, YC065-YD157
0007	20		CQ		3-1	33-12-12	D00139	K			TB0506Y	A011	1A		YC059-YC064
0007	20		PA		2-11	33-12-12	D00139	K			TB0506Y	A011	1A		YD158, YL951-YR328
0008	24		PK		29-4	23-43-11	D00141	7			D04153P	A16			YC051-YC052
0008	24		PK		28-11	23-43-11	D00141	7			D04153P	A16			YC053-YC055
0008	24		PK		28-10	23-43-11	D00141	7			D04153P	A16			YC056-YD157
0010	22		CQ		29-4	23-27-11	D00141	CAP	Y		D04153P	CAP	Y		YC051-YC052
0010	22		CQ		28-11	23-27-11	D00141	CAP	Y		D04153P	CAP	Y		YC053
0010	22		CQ		28-11	23-27-11	D00141	13			D04153P	A14			YC054-YC055
0010	22		CQ		28-10	23-27-11	D00141	13			D04153P	A14			YC056-YD157
0011	20		PA		2-8	23-51-31	GD00508	ST..	1A		D00139			FA	YC051-YC052
0011	20		PA		2-4	23-51-31	GD00508	ST..	1A		D00139			FA	YC053-YD158, YL951-YR328
0012	20		CQ		3-0	33-18-42	D00139	N			TB0502Y	B011	1A		YC051-YC058
0012	20		CQ		3-2	33-18-42	D00139	N			TB0502Y	B011	1A		YC059-YD158, YL951-YR328
0013	20		CQ		2-10	33-12-12	D00139	L			TB0502Y	A019	1A		YC051-YC052
0013	20		CQ		3-1	33-12-12	D00139	L			TB0502Y	A019	1A		YC053-YC058, YC065-YD157
0013	20		CQ		3-2	33-12-12	D00139	L			TB0502Y	A019	1A		YC059-YC064
0013	20		PA		3-1	33-12-12	D00139	L			TB0502Y	A019	1A		YD158
0013	20		PA		2-10	33-12-12	D00139	L			TB0506X	A015	1A		YL951-YR328
0016	22		PA		4-6	23-51-31	D00139	E			GD00505	DC..	1A		YC051-YC052
0016	22		PA		3-10	23-51-31	D00139	E			GD00520	DC..	1A		YC053-YC058
0016	22		PA		4-2	23-51-31	D00139	E			GD00520	DC..	1A		YC059-YD157
0017	24		B6		29-4	23-22-11	D00141	1			D04153P	A09			YC051-YC052
0017	24		B6		28-11	23-22-11	D00141	1			D04153P	A09			YC053-YC055
0017	24		B6		28-10	23-22-11	D00141	1			D04153P	A09			YC056-YD157
0018	24		B6		29-4	23-22-11	D00141	2			D04153P	A10			YC051-YC052
0018	24		B6		28-11	23-22-11	D00141	2			D04153P	A10			YC053-YC055
0018	24		B6		28-10	23-22-11	D00141	2			D04153P	A10			YC056-YD157
0019	24		B6		29-4	23-22-11	D00141	3			D04153P	A13			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W3320

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W3327	286A3327				F/OBS FLIGHT INPH (continued)												
0019	24	B6			28-11	23-22-11	D00141		3			D04153P	A13			YC053-YC055	
0019	24	B6			28-10	23-22-11	D00141		3			D04153P	A13			YC056-YD157	
0020	24	B6			29-4	23-22-11	D00141		4			D04153P	A12			YC051-YC052	
0020	24	B6			28-11	23-22-11	D00141		4			D04153P	A12			YC053-YC055	
0020	24	B6			28-10	23-22-11	D00141		4			D04153P	A12			YC056-YD157	
0029	20	CQ			3-0	33-18-42	D00141		15			TB0502Z	A001	1A		YC051-YC052	
0029	20	CQ			2-9	33-18-42	D00141		15			TB0503Z	A001	1A		YC054-YC058	
0029	20	CQ			2-11	33-18-42	D00141		15			TB0503Z	A001	1A		YC059-YC064	
0029	20	CQ			3-1	33-18-42	D00141		15			TB0503Z	A001	1A		YC065-YD157	
0030	22	PA			0-7	23-51-31	D00139		F			D00139	G			YC051-YD158, YL951-YR328	
0031	20	CQ			3-1	33-18-42	D00139		M			TB0503Z	A001	1A		YD158, YL951-YR328	
0033	24	PK			29-4	23-15-15	D00141		19			D04153P	B10			YC051-YC052	
0033	24	PK			28-11	23-15-15	D00141		19			D04153P	B10			YC053-YC055	
0033	24	PK			28-10	23-15-15	D00141		19			D04153P	B10			YC056-YD157	
0034	24	PK			29-4	23-15-15	D00141		20			D04153P	B16			YC051-YC052	
0034	24	PK			28-11	23-15-15	D00141		20			D04153P	B16			YC053-YC055	
0034	24	PK			28-10	23-15-15	D00141		20			D04153P	B16			YC056-YD157	
0035	24	PK			29-4	23-15-15	D00141		10			D04153P	B12			YC051-YC052	
0035	24	PK			28-11	23-15-15	D00141		10			D04153P	B12			YC053-YC055	
0035	24	PK			28-10	23-15-15	D00141		10			D04153P	B12			YC056-YD157	
0036	24	PK			29-4	23-15-15	D00141		14			D04153P	B14			YC051-YC052	
0036	24	PK			28-11	23-15-15	D00141		14			D04153P	B14			YC053-YC055	
0036	24	PK			28-10	23-15-15	D00141		14			D04153P	B14			YC056-YD157	
0037	22	PA			2-8	23-15-15	D00141		18			GD00508	DC..	1A		YC051-YC052	
0037	22	PA			2-3	23-15-15	D00141		18			GD00508	DC..	1A		YC053-YC058	
0037	22	PA			2-4	23-15-15	D00141		18			GD00508	DC..	1A		YC059-YD157	
2501B	24	Y2	AA		26-7	23-51-31	D04153P		B06			D04151P	2			YC051-YC052, YC056-YD158, YL951-YR328	
2501B	24	Y2	AA		26-8	23-51-31	D04153P		B06			D04151P	2			YC053-YC055	
2501R	24	Y2	AA		0-0	23-51-31	D04153P		A06			D04151P	1			YC051-YD158, YL951-YR328	
2501Z			AA		0-0	23-51-31	D04153P		PERG	1F		D04151P	DED			YC051-YD158, YL951-YR328	
2502B	24	Y2	AB		26-7	23-51-31	D04153P		B07			D04151P	4			YC051-YC052, YC056-YD158, YL951-YR328	
2502B	24	Y2	AB		26-8	23-51-31	D04153P		B07			D04151P	4			YC053-YC055	

WIRE LIST

D280A108

91-21-11

Section W3320

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From			To			Effectivity			
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W3327	286A3327			F/OBS FLIGHT INPH (continued)												
2502R	24	Y2	AB		0-0	23-51-31	D04153P	A07			D04151P	3			YC051-YD158, YL951-YR328	
2502Z			AB		0-0	23-51-31	D04153P	PERG	1F		D04151P	DED			YC051-YD157	
2502Z			AB		0-0	23-51-31	D04153P	B05			D04151P	DED			YD158, YL951-YR328	
2503B	24	Y2	AC		29-4	23-51-31	D04153P	B01			D00139	B			YC051-YC052	
2503B	24	Y2	AC		29-0	23-51-31	D04153P	B01			D00139	B			YC053-YC055	
2503B	24	Y2	AC		28-11	23-51-31	D04153P	B01			D00139	B			YC056-YC058	
2503B	24	Y2	AC		28-10	23-51-31	D04153P	B01			D00139	B			YC059-YD158, YL951-YR328	
2503R	24	Y2	AC		0-0	23-51-31	D04153P	A01			D00139	A			YC051-YD158, YL951-YR328	
2503Z			AC		0-0	23-51-31	D04153P	B02			D00139			FA	YC051-YD157	
2503Z			AC		0-0	23-51-31	D04153P	PERG	1F		D00139			FA	YD158, YL951-YR328	
2504B	24	Y2	AE		32-9	23-51-31	D04153P	B11			SM00008		9		YC051-YC052	
2504B	24	Y2	AE		32-2	23-51-31	D04153P	B11			SM00008		9		YC053-YC055	
2504B	24	Y2	AE		32-1	23-51-31	D04153P	B11			SM00008		9		YC056-YD158	
2504R	24	Y2	AE		0-0	23-51-31	D04153P	A11			SM00007		9		YC051-YD158	
2504Z			AE		0-0	23-51-31	D04153P	PERG	1F		SM00REF	DED			YC051-YD158	
3501B	24	Y3	AD		26-7	23-51-31	D04153P	B08			D04151P	6			YC051-YC052, YC056-YD158, YL951-YR328	
3501B	24	Y3	AD		26-8	23-51-31	D04153P	B08			D04151P	6			YC053-YC055	
3501R	24	Y3	AD		0-0	23-51-31	D04153P	A08			D04151P	5			YC051-YD158, YL951-YR328	
3501Y	24	Y3	AD		0-0	23-51-31	D04153P	B09			D04151P	7			YC051-YD158, YL951-YR328	
3501Z			AD		0-0	23-51-31	D04153P	PERG	1F		D04151P	DED			YC051-YD157	
3501Z			AD		0-0	23-51-31	D04153P	A09			D04151P	DED			YD158, YL951-YR328	
3509B	24	Y3	AS		26-7	23-51-31	D04151P	10			D04153P	A18			YD158, YL951-YR328	
3509R	24	Y3	AS		0-0	23-51-31	D04151P	9			D04153P	B17			YD158, YL951-YR328	
3509Y	24	Y3	AS		0-0	23-51-31	D04151P	8			D04153P	A17			YD158, YL951-YR328	
3509Z			AS		0-0	23-51-31	D04151P	DED			D04153P	B18			YD158, YL951-YR328	
C-CA			VC		0-0	23-51-31	D06037	BLU			SM00007		9		YC051-YD158	
C-CB			VC		0-0	23-51-31	D06037	BLK			SM00008		9		YC051-YD158	
W3329	286A3329			VOICE RECORDER CONTROL PNL												
0001	22	PA			34-8	23-71-01	D00179	H			D04157P	A01			YC051-YC052, YC065-YR328	
0001	22	PA			34-7	23-71-01	D00179	H			D04157P	A01			YC053-YC055	

WIRE LIST

D280A108

91-21-11

Section W3320

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W3329	286A3329				VOICE RECORDER CONTROL PNL (continued)											
0001	22		PA		34-5	23-71-01		D00179		H		D04157P	A01			YC056-YC058
0001	22		PA		34-6	23-71-01		D00179		H		D04157P	A01			YC059-YC064
0002	22		PA		34-8	23-71-01		D00179		G		D04157P	B01			YC051-YC052, YC065-YR328
0002	22		PA		34-7	23-71-01		D00179		G		D04157P	B01			YC053-YC055
0002	22		PA		34-5	23-71-01		D00179		G		D04157P	B01			YC056-YC058
0002	22		PA		34-6	23-71-01		D00179		G		D04157P	B01			YC059-YC064
0003	22		PA		0-3	23-71-01		D00179		Q-		D00179	R-			ALL
0004	22		PA		0-3	23-71-01		D00179		F-		D00179	N			ALL
0005	22		PA		0-3	23-71-01		D00179		G-		D00179	P			ALL
0010	24		PK		34-8	23-71-01		D00179		C		D04157P	A02			YC051-YC052, YC065-YR328
0010	24		PK		34-7	23-71-01		D00179		C		D04157P	A02			YC053-YC055
0010	24		PK		34-5	23-71-01		D00179		C		D04157P	A02			YC056-YC058
0010	24		PK		34-6	23-71-01		D00179		C		D04157P	A02			YC059-YC064
0011	24		PK		34-8	23-71-01		D00179		B		D04157P	B02			YC051-YC052, YC065-YR328
0011	24		PK		34-7	23-71-01		D00179		B		D04157P	B02			YC053-YC055
0011	24		PK		34-5	23-71-01		D00179		B		D04157P	B02			YC056-YC058
0011	24		PK		34-6	23-71-01		D00179		B		D04157P	B02			YC059-YC064
0012	24		PK		34-8	23-71-01		D00179		E		D04157P	A03			YC051-YC052, YC065-YR328
0012	24		PK		34-7	23-71-01		D00179		E		D04157P	A03			YC053-YC055
0012	24		PK		34-5	23-71-01		D00179		E		D04157P	A03			YC056-YC058
0012	24		PK		34-6	23-71-01		D00179		E		D04157P	A03			YC059-YC064
0013	24		PK		34-8	23-71-01		D00179		D		D04157P	B03			YC051-YC052, YC065-YL959, YN231-YN235
0013	24		PK		34-7	23-71-01		D00179		D		D04157P	B03			YC053-YC055
0013	24		PK		34-5	23-71-01		D00179		D		D04157P	B03			YC056-YC058
0013	24		PK		34-6	23-71-01		D00179		D		D04157P	B03			YC059-YC064
0013	24		PK		14-6	23-71-01		D00179		D		SP00867		W		YL963-YL999, YN236-YR328
0014	24		PK		34-8	23-71-01		D00179		A		D04157P	A04			YC051-YC052, YC065-YR328
0014	24		PK		34-7	23-71-01		D00179		A		D04157P	A04			YC053-YC055
0014	24		PK		34-5	23-71-01		D00179		A		D04157P	A04			YC056-YC058
0014	24		PK		34-6	23-71-01		D00179		A		D04157P	A04			YC059-YC064

WIRE LIST

D280A108

91-21-11

Section W3320

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3329	286A3329				VOICE RECORDER CONTROL PNL (continued)										
0015	22		PA		34-8	23-71-01	D00179		F		D04157P	B04			YC051-YC052, YC065-YR328
0015	22		PA		34-7	23-71-01	D00179		F		D04157P	B04			YC053-YC055
0015	22		PA		34-5	23-71-01	D00179		F		D04157P	B04			YC056-YC058
0015	22		PA		34-6	23-71-01	D00179		F		D04157P	B04			YC059-YC064
2001B	24		Y2	AA	34-8	23-71-01	D00179		K		D04157P	B05			YC051-YC052, YC065-YR328
2001B	24		Y2	AA	34-7	23-71-01	D00179		K		D04157P	B05			YC053-YC055
2001B	24		Y2	AA	34-5	23-71-01	D00179		K		D04157P	B05			YC056-YC058
2001B	24		Y2	AA	34-6	23-71-01	D00179		K		D04157P	B05			YC059-YC064
2001R	24		Y2	AA	0-0	23-71-01	D00179		L		D04157P	A05			ALL
2001Z				AA	0-0	23-71-01	D00179	DED			D04157P	B06			ALL
2002B	24		PL	AB	34-8	23-71-01	D00179		V		D04157P	B07			YC051-YC052, YC065-YR328
2002B	24		PL	AB	34-7	23-71-01	D00179		V		D04157P	B07			YC053-YC055
2002B	24		PL	AB	34-5	23-71-01	D00179		V		D04157P	B07			YC056-YC058
2002B	24		PL	AB	34-6	23-71-01	D00179		V		D04157P	B07			YC059-YC064
2002R	24		PL	AB	0-0	23-71-01	D00179		W		D04157P	A07			ALL
2003B	24		PL	AE	34-8	23-71-01	D00179		I-	VP	D04157P	B08			YC051-YC052, YC065-YD170
2003B	24		PL	AE	34-7	23-71-01	D00179		I-	VP	D04157P	B08			YC053-YC055
2003B	24		PL	AE	34-5	23-71-01	D00179		I-	VP	D04157P	B08			YC056-YC058
2003B	24		PL	AE	34-6	23-71-01	D00179		I-	VP	D04157P	B08			YC059-YC064
2003B	24		PL	AE	34-8	23-71-01	D00179		I-		D04157P	B08			YL951-YL959, YN231-YN235
2003R	24		PL	AE	0-0	23-71-01	D00179	H-	VP		D04157P	A08			YC051-YD170
2003R	24		PL	AE	0-0	23-71-01	D00179	H-			D04157P	A08			YL951-YL959, YN231-YN235
2005B	24		Y2	AC	33-7	23-41-11	S00050		2	C	D04157P	B09			YC051-YC055
2005B	24		Y2	AC	33-4	23-41-11	S00050		2	C	D04157P	B09			YC056-YC058
2005B	24		Y2	AC	33-6	23-41-11	S00050		2	C	D04157P	B09			YC059-YC064
2005B	24		Y2	AC	33-8	23-41-11	S00050		2	C	D04157P	B09			YC065-YR328
2005R	24		Y2	AC	0-0	23-41-11	S00050		1	C	D04157P	A09			ALL
2005Z				AC	0-0	23-41-11	S00050	DED			D04157P	PERG	1F		ALL
2006B	22		PB	AD	37-3	23-31-02	SP00135			S	D04157P	B10			YC051-YC052
2006B	22		PB	AD	37-4	23-31-02	SP00135			S	D04157P	B10			YC053-YC055
2006B	22		PB	AD	37-2	23-31-02	SP00135			S	D04157P	B10			YC056-YC058
2006B	22		PB	AD	37-6	23-31-02	SP00135			S	D04157P	B10			YC059-YC064
2006B	22		PB	AD	37-8	23-31-02	SP00135			S	D04157P	B10			YC065-YR328

WIRE LIST

D280A108

91-21-11

Section W3320

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3329																
		286A3329			VOICE RECORDER CONTROL PNL (continued)											
2006R		22		PB	AD	0-0	23-31-02	SP00133		S		D04157P	A10			ALL

For training purposes only!

WIRE LIST
D280A108

91-21-11
Section W3320
Page 10 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Diagram	From				To				Effectivity	
	Wire No.	GA	CO TY			Fam	FT-IN	Equip	Term	Type	Splice	Equip	Term		Type
W3335	286A3335			AUDIO ENTERTAINMENT - RH SIDE - FWD											
0001	20		PA		55-8	23-34-02	D48335P	10			D08427J	10			YC051-YC055
0001	20		PA		56-2	23-34-02	D48335P	10			D08427J	10			YC056-YD157
0001	22		PA		56-1	23-34-02	D48335P	7			D08427J	10			YD158-YD170
0002	22		PA		55-8	23-34-02	D48335P	11			D08427J	11			YC051-YC055
0002	22		PA		56-2	23-34-02	D48335P	11			D08427J	11			YC056-YD157
0002	22		PA		85-3	23-34-02	D48335P	14			D08537J	10			YD158-YD170
0003	22		PA		55-8	23-34-02	D48335P	12			D08427J	12			YC051-YC055
0003	22		PA		56-2	23-34-02	D48335P	12			D08427J	12			YC056-YD157
0003	22		PA		21-4	23-34-02	D48339P	7			D08429J	10			YD158-YD170
0004	22		PA		55-8	23-34-02	D48335P	13			D08427J	13			YC051-YC055
0004	22		PA		56-2	23-34-02	D48335P	13			D08427J	13			YC056-YD157
0004	22		PA		94-3	23-34-02	D48339P	14			D08539J	10			YD158-YD170
0005	20		PA		124-0	23-34-02	D48333P	B02			D10587	8			YD158-YD170
0006	20		PA		9-2	23-34-02	GD03736	ST..	1		D10587	11			YD158-YD170
0007	20		PA		9-2	23-34-02	GD03736	AC..	1		D10587	6			YD158-YD170
2501B	24		W9	AA	55-8	23-34-02	D48335P	5			D08427J	2			YC051-YC055
2501B	24		W9	AA	56-2	23-34-02	D48335P	5			D08427J	2			YC056-YD157
2501B	24		W9	AA	56-1	23-34-02	D48335P	2			D08427J	4			YD158-YD170
2501W	24		W9	AA	0-0	23-34-02	D48335P	4			D08427J	1			YC051-YD157
2501W	24		W9	AA	0-0	23-34-02	D48335P	1			D08427J	5			YD158-YD170
2501Z				AA	0-0	23-34-02	D48335P	6			D08427J	3			YC051-YD157
2501Z				AA	0-0	23-34-02	D48335P	PERB			D08427J	PERB			YD158-YD170
2502B	24		W9	AB	55-8	23-34-02	D48335P	2			D08427J	5			YC051-YC055
2502B	24		W9	AB	56-2	23-34-02	D48335P	2			D08427J	5			YC056-YD157
2502B	24		W9	AB	56-1	23-34-02	D48335P	4			D08427J	2			YD158-YD170
2502W	24		W9	AB	0-0	23-34-02	D48335P	1			D08427J	4			YC051-YD157
2502W	24		W9	AB	0-0	23-34-02	D48335P	3			D08427J	1			YD158-YD170
2502Z				AB	0-0	23-34-02	D48335P			AB	D08427J			AC	YC051-YD157
2502Z				AB	0-0	23-34-02	D48335P	PERB			D08427J	PERB			YD158-YD170
2503B	20		X2	AC	55-8	23-34-02	D48335P	15			D08427J	15			YC051-YC055
2503B	20		X2	AC	56-2	23-34-02	D48335P	15			D08427J	15			YC056-YD157
2503B	20		X2	AC	56-1	23-34-02	D48335P	6			D08427J	15			YD158-YD170
2503R	20		X2	AC	0-0	23-34-02	D48335P	14			D08427J	14			YC051-YD157
2503R	20		X2	AC	0-0	23-34-02	D48335P	5			D08427J	14			YD158-YD170
2503Z				AC	0-0	23-34-02	D48335P	DED			D08427J	DED			YC051-YD157
2503Z				AC	0-0	23-34-02	D48335P	PERB			D08427J	PERB			YD158-YD170
2504B	24		W9	AD	55-8	23-34-02	D48335P	8			D08427J	8			YC051-YC055
2504B	24		W9	AD	56-2	23-34-02	D48335P	8			D08427J	8			YC056-YD157
2504B	24		W9	AD	85-3	23-34-02	D48335P	9			D08537J	4			YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W3330

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description		From				To					
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3335	286A3335			AUDIO ENTERTAINMENT - RH SIDE - FWD (continued)											
2504W	24		W9	AD	0-0	23-34-02	D48335P	7			D08427J	7			YC051-YD157
2504W	24		W9	AD	0-0	23-34-02	D48335P	8			D08537J	5			YD158-YD170
2504Z				AD	0-0	23-34-02	D48335P			AB	D08427J			AC	YC051-YD157
2504Z				AD	0-0	23-34-02	D48335P		PERB		D08537J		PERB		YD158-YD170
2505B	24		W9	AE	85-3	23-34-02	D48335P	11			D08537J	2			YD158-YD170
2505W	24		W9	AE	0-0	23-34-02	D48335P	10			D08537J	1			YD158-YD170
2505Z				AE	0-0	23-34-02	D48335P		PERB		D08537J		PERB		YD158-YD170
2506B	20		X2	AF	85-3	23-34-02	D48335P	13			D08537J	15			YD158-YD170
2506R	20		X2	AF	0-0	23-34-02	D48335P	12			D08537J	14			YD158-YD170
2506Z				AF	0-0	23-34-02	D48335P		PERB		D08537J		PERB		YD158-YD170
2507B	24		W9	AG	21-4	23-34-02	D48339P	2			D08429J	4			YD158-YD170
2507W	24		W9	AG	0-0	23-34-02	D48339P	1			D08429J	5			YD158-YD170
2507Z				AG	0-0	23-34-02	D48339P		PERB		D08429J		PERB		YD158-YD170
2508B	24		W9	AH	21-4	23-34-02	D48339P	4			D08429J	2			YD158-YD170
2508W	24		W9	AH	0-0	23-34-02	D48339P	3			D08429J	1			YD158-YD170
2508Z				AH	0-0	23-34-02	D48339P		PERB		D08429J		PERB		YD158-YD170
2509B	20		X2	AI	21-4	23-34-02	D48339P	6			D08429J	15			YD158-YD170
2509R	20		X2	AI	0-0	23-34-02	D48339P	5			D08429J	14			YD158-YD170
2509Z				AI	0-0	23-34-02	D48339P		PERB		D08429J		PERB		YD158-YD170
2510B	24		W9	AJ	94-3	23-34-02	D48339P	9			D08539J	4			YD158-YD170
2510W	24		W9	AJ	0-0	23-34-02	D48339P	8			D08539J	5			YD158-YD170
2510Z				AJ	0-0	23-34-02	D48339P		PERB		D08539J		PERB		YD158-YD170
2511B	24		W9	AK	94-3	23-34-02	D48339P	11			D08539J	2			YD158-YD170
2511W	24		W9	AK	0-0	23-34-02	D48339P	10			D08539J	1			YD158-YD170
2511Z				AK	0-0	23-34-02	D48339P		PERB		D08539J		PERB		YD158-YD170
2512B	20		X2	AL	94-3	23-34-02	D48339P	13			D08539J	15			YD158-YD170
2512R	20		X2	AL	0-0	23-34-02	D48339P	12			D08539J	14			YD158-YD170
2512Z				AL	0-0	23-34-02	D48339P		PERB		D08539J		PERB		YD158-YD170
3501B	22		X3	HA	124-0	23-34-02	D48333P	B01			D10587	2			YD158-YD170
3501R	22		X3	HA	0-0	23-34-02	D48333P	A01			D10587	1			YD158-YD170
3501Y	22		X3	HA	0-0	23-34-02	D48333P	A02			D10587	9			YD158-YD170
3501Z				HA	0-0	23-34-02	D48333P		PERG	1F	D10587		PERB		YD158-YD170
FRAB					0-0	23-34-02	D48335P				D48335P	3			YC051-YD157
FRAC					0-0	23-34-02	D08427J			AB	D08427J	6			YC051-YD157
YAAA					0-0	23-34-02	D48335P		PERB	AC	D08427J		PERB		YC051-YD157
YAAA					0-0	23-34-02	D48335P		PERB		OAS0001				YD158-YD170
YAAB					0-0	23-34-02	D08427J		PERB		OAS0003				YD158-YD170
YAAC					0-0	23-34-02	D08537J		PERB		OAS0004				YD158-YD170
YAAD					0-0	23-34-02	D48339P		PERB		OAS0001				YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W3330

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3335		286A3335			AUDIO ENTERTAINMENT - RH SIDE - FWD (continued)											
YAAE						0-0	23-34-02	D08429J		PERB		OAS0002				YD158-YD170
YAAF						0-0	23-34-02	D08539J		PERB		OAS0004				YD158-YD170
YAAG						0-0	23-34-02	OAS0001				OAS0002				YD158-YD170
YAAH						0-0	23-34-02	OAS0002				OAS0003				YD158-YD170
YAAJ						0-0	23-34-02	OAS0003				OAS0004				YD158-YD170
W3339		286A3339			AUDIO ENTERTAINMENT - LH SIDE - FWD											
0001		20		PA		21-5	23-34-02	D48339P		10		D08429J		10		YC051-YC055
0001		20		PA		21-3	23-34-02	D48339P		10		D08429J		10		YC056-YD157
0002		22		PA		21-5	23-34-02	D48339P		11		D08429J		11		YC051-YC055
0002		22		PA		21-3	23-34-02	D48339P		11		D08429J		11		YC056-YD157
0003		22		PA		21-5	23-34-02	D48339P		12		D08429J		12		YC051-YC055
0003		22		PA		21-3	23-34-02	D48339P		12		D08429J		12		YC056-YD157
0004		22		PA		21-5	23-34-02	D48339P		13		D08429J		13		YC051-YC055
0004		22		PA		21-3	23-34-02	D48339P		13		D08429J		13		YC056-YD157
2501B		24		W9	AA	21-5	23-34-02	D48339P		5		D08429J		2		YC051-YC055
2501B		24		W9	AA	21-3	23-34-02	D48339P		5		D08429J		2		YC056-YD157
2501W		24		W9	AA	0-0	23-34-02	D48339P		4		D08429J		1		YC051-YD157
2501Z					AA	0-0	23-34-02	D48339P		6		D08429J		3		YC051-YD157
2502B		24		W9	AB	21-5	23-34-02	D48339P		2		D08429J		5		YC051-YC055
2502B		24		W9	AB	21-3	23-34-02	D48339P		2		D08429J		5		YC056-YD157
2502W		24		W9	AB	0-0	23-34-02	D48339P		1		D08429J		4		YC051-YD157
2502Z					AB	0-0	23-34-02	D48339P			AB	D08429J			AC	YC051-YD157
2503B		20		X2	AC	21-5	23-34-02	D48339P		15		D08429J		15		YC051-YC055
2503B		20		X2	AC	21-3	23-34-02	D48339P		15		D08429J		15		YC056-YD157
2503R		20		X2	AC	0-0	23-34-02	D48339P		14		D08429J		14		YC051-YD157
2503Z					AC	0-0	23-34-02	D48339P		DED		D08429J		DED		YC051-YD157
2504B		24		W9	AD	21-5	23-34-02	D48339P		8		D08429J		8		YC051-YC055
2504B		24		W9	AD	21-3	23-34-02	D48339P		8		D08429J		8		YC056-YD157
2504W		24		W9	AD	0-0	23-34-02	D48339P		7		D08429J		7		YC051-YD157
2504Z					AD	0-0	23-34-02	D48339P			AB	D08429J			AC	YC051-YD157
FRAB						0-0	23-34-02	D48339P			AB	D48339P		3		YC051-YD157
FRAC						0-0	23-34-02	D08429J			AC	D08429J		6		YC051-YD157
YAAA						0-0	23-34-02	D48339P		PERB		D08429J		PERB		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W3330

Page 3 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3349	286A3349				VIDEO - VCC TO DISC BRACKET (NEAR TRAY 3) AND TO AB085										
0001	20		PA		16-7	23-32-21	D45145J	16			D45297P	16			YN231-YN235
0003	20		PA		16-2	23-32-11	D45139J	3			D45289P	3			YN231-YN260
0004	20		PA		16-9	23-32-11	D45139J	4			GD04270	DC..	1		YN231-YN260
0005	20		PA		16-9	23-32-11	D45139J	5			GD04270	ST..	1		YN231-YN260
0006	22		PA		17-0	23-32-14	D45285P	20			D45129J	20			YN231-YN260
0007	22		CQ		17-0	23-32-14	D45129J	21			D45285P	21			YN231-YN260
0009	22		PA		17-0	23-32-12	D45129J	28			D45285P	28			YN231-YN260
0010	22		PA		17-0	23-32-12	D45129J	22			D45285P	22			YN231-YN260
0011	22		PA		17-0	23-32-12	D45129J	30			D45285P	30			YN231-YN260
0012	22		PA		17-0	23-32-12	D45129J	27			D45285P	27			YN231-YN260
0015	22		PA		17-0	23-32-14	D45129J	38			D45285P	38			YN231-YN260
0016	20		PA		16-9	23-32-13	D45139J	31			GD04270	ST..	1		YN231-YN260
0017	22		PA		17-0	23-32-14	D45129J	35			D45285P	35			YN231-YN260
001CO				IA	0-0	23-32-21	D45297P	= 15			D45145J	= 15			YN231-YN260
001CX			0F	IA	16-1	23-32-21	D45297P	15			D45145J	15			YN231-YN260
0030	22		PA		17-0	23-32-14	D45129J	47			D45285P	47			YN231-YN260
0086	22		PA		17-0	23-32-14	D45129J	46			D45285P	46			YN231-YN260
0087	22		PA		17-0	23-32-14	D45129J	34			D45285P	34			YN231-YN260
2001B	20		PB	EA	16-2	23-32-11	D45289P	2			D45139J	2			YN231-YN260
2001R	20		PB	EA	0-0	23-32-11	D45289P	1			D45139J	1			YN231-YN260
2501B	22		X2	AA	17-0	23-32-12	D45129J	6			D45285P	6			YN231-YN260
2501R	22		X2	AA	0-0	23-32-12	D45129J	5			D45285P	5			YN231-YN260
2501Z				AA	0-0	23-32-12	D45129J			AA	D45285P			AB	YN231-YN260
2502B	22		X2	AB	17-0	23-32-12	D45129J	8			D45285P	8			YN231-YN260
2502R	22		X2	AB	0-0	23-32-12	D45129J	7			D45285P	7			YN231-YN260
2502Z				AB	0-0	23-32-12	D45129J			AA	D45285P			AB	YN231-YN260
2503B	22		X2	AC	17-0	23-32-12	D45129J	10			D45285P	10			YN231-YN260
2503R	22		X2	AC	0-0	23-32-12	D45129J	9			D45285P	9			YN231-YN260
2503Z				AC	0-0	23-32-12	D45129J			AA	D45285P			AB	YN231-YN260
2504B	22		X2	AD	17-0	23-32-12	D45129J	13			D45285P	13			YN231-YN260
2504R	22		X2	AD	0-0	23-32-12	D45129J	12			D45285P	12			YN231-YN260
2504Z				AD	0-0	23-32-12	D45129J			AC	D45285P			AD	YN231-YN260
2505B	22		X2	AE	17-0	23-32-12	D45129J	15			D45285P	15			YN231-YN260
2505R	22		X2	AE	0-0	23-32-12	D45129J	14			D45285P	14			YN231-YN260
2505Z				AE	0-0	23-32-12	D45129J			AC	D45285P			AD	YN231-YN260
2506B	22		X2	AF	17-0	23-32-12	D45129J	17			D45285P	17			YN231-YN260
2506R	22		X2	AF	0-0	23-32-12	D45129J	16			D45285P	16			YN231-YN260
2506Z				AF	0-0	23-32-12	D45129J			AC	D45285P			AD	YN231-YN260
2507B	22		X2	AG	17-0	23-32-12	D45129J	3			D45285P	3			YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W3340

Page 1

Aug 14/2012

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type
W3349	286A3349			VIDEO - VCC TO DISC BRACKET (NEAR TRAY 3) AND TO AB0858 (continued)										
2507R	22	X2	AG	0-0	23-32-12	D45129J	2			D45285P	2			YN231-YN260
2507Z			AG	0-0	23-32-12	D45129J	4			D45285P	4			YN231-YN260
2508B	22	X2	AH	17-0	23-32-12	D45129J	25			D45285P	25			YN231-YN260
2508R	22	X2	AH	0-0	23-32-12	D45129J	24			D45285P	24			YN231-YN260
2508Z			AH	0-0	23-32-12	D45129J	26			D45285P	26			YN231-YN260
2510B	24	0T	AJ	16-2	23-32-31	D45289P	7			D45139J	7			YN231-YN260
2510W	24	0T	AJ	0-0	23-32-31	D45289P	6			D45139J	6			YN231-YN260
2510Z			AJ	0-0	23-32-31	D45289P	8			D45139J	8			YN231-YN260
2511B	24	7P	AK	16-2	23-32-31	D45139J	9			D45289P	9			YN231-YN260
2511BN	24	7P	AK	0-0	23-32-31	D45139J	10			D45289P	10			YN231-YN260
2511Z			AK	0-0	23-32-31	D45139J	11			D45289P	11			YN231-YN260
2512B	24	7P	AL	16-2	23-32-31	D45139J	12			D45289P	12			YN231-YN260
2512BN	24	7P	AL	0-0	23-32-31	D45139J	13			D45289P	13			YN231-YN260
2512Z			AL	0-0	23-32-31	D45139J	14			D45289P	14			YN231-YN260
2513B	24	7P	AM	16-2	23-32-31	D45139J	15			D45289P	15			YN231-YN260
2513BN	24	7P	AM	0-0	23-32-31	D45139J	16			D45289P	16			YN231-YN260
2513Z			AM	0-0	23-32-31	D45139J	17			D45289P	17			YN231-YN260
2514B	24	0T	AN	16-2	23-32-51	D45139J	19			D45289P	19			YN231-YN260
2514W	24	0T	AN	0-0	23-32-51	D45139J	18			D45289P	18			YN231-YN260
2514Z			AN	0-0	23-32-51	D45139J	20			D45289P	20			YN231-YN260
2515B	24	7P	AP	16-2	23-32-51	D45139J	21			D45289P	21			YN231-YN260
2515BN	24	7P	AP	0-0	23-32-51	D45139J	22			D45289P	22			YN231-YN260
2515Z			AP	0-0	23-32-51	D45139J	23			D45289P	23			YN231-YN260
2516B	24	7P	AQ	16-2	23-32-51	D45139J	24			D45289P	24			YN231-YN260
2516BN	24	7P	AQ	0-0	23-32-51	D45139J	25			D45289P	25			YN231-YN260
2516Z			AQ	0-0	23-32-51	D45139J	26			D45289P	26			YN231-YN260
2517B	24	7P	AR	16-2	23-32-51	D45139J	27			D45289P	27			YN231-YN260
2517BN	24	7P	AR	0-0	23-32-51	D45139J	28			D45289P	28			YN231-YN260
2517Z			AR	0-0	23-32-51	D45139J	29			D45289P	29			YN231-YN260
2518B	24	0T	AS	17-0	23-32-12	D45129J	54			D45285P	54			YN231-YN260
2518W	24	0T	AS	0-0	23-32-12	D45129J	53			D45285P	53			YN231-YN260
2518Z			AS	0-0	23-32-12	D45129J	55			D45285P	55			YN231-YN260
2521B	24	0T	AV	16-7	23-32-21	D45297P	3			D45145J	3			YN231-YN260
2521W	24	0T	AV	0-0	23-32-21	D45297P	2			D45145J	2			YN231-YN260
2521Z			AV	0-0	23-32-21	D45297P	4			D45145J	4			YN231-YN260
2522B	24	7P	AW	16-7	23-32-21	D45297P	5			D45145J	5			YN231-YN260
2522BN	24	7P	AW	0-0	23-32-21	D45297P	6			D45145J	6			YN231-YN260
2522Z			AW	0-0	23-32-21	D45297P	7			D45145J	7			YN231-YN260
2523B	24	Y2	AX	16-7	23-32-21	D45297P	9			D45145J	9			YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W3340

Page 2

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3349	286A3349			VIDEO - VCC TO DISC BRACKET (NEAR TRAY 3) AND TO AB0858 (continued)											
2523R	24	Y2	AX		0-0	23-32-21	D45297P		8		D45145J		8		YN231-YN260
2523Z			AX		0-0	23-32-21	D45297P		10		D45145J		10		YN231-YN260
2524B	24	Y2	AY		16-7	23-32-21	D45297P		22		D45145J		21		YN231-YN260
2524R	24	Y2	AY		0-0	23-32-21	D45297P		21		D45145J		22		YN231-YN260
2524Z			AY		0-0	23-32-21	D45297P		23		D45145J		23		YN231-YN260
2525B	24	Y2	AZ		16-7	23-32-21	D45297P		20		D45145J		20		YN231-YN260
2525R	24	Y2	AZ		0-0	23-32-21	D45297P		19		D45145J		19		YN231-YN260
2525Z			AZ		0-0	23-32-21	D45297P		24		D45145J		24		YN231-YN260
2526B	24	Y2	BA		16-7	23-32-21	D45297P		18		D45145J		18		YN231-YN260
2526R	24	Y2	BA		0-0	23-32-21	D45297P		17		D45145J		17		YN231-YN260
2526Z			BA		0-0	23-32-21	D45297P		25		D45145J		25		YN231-YN260
3001B	22	PC	GA		17-0	23-32-12	D45129J		32		D45285P		32		YN231-YN260
3001R	22	PC	GA		0-0	23-32-12	D45129J		31		D45285P		31		YN231-YN260
3001Y	22	PC	GA		0-0	23-32-12	D45129J		33		D45285P		33		YN231-YN260
FRAA					0-0	23-32-12	D45129J			AA	D45129J		11		YN231-YN260
FRAB					0-0	23-32-12	D45285P			AB	D45285P		11		YN231-YN260
FRAC					0-0	23-32-12	D45129J			AC	D45129J		18		YN231-YN260
FRAD					0-0	23-32-12	D45285P			AD	D45285P		18		YN231-YN260

WIRE LIST

D280A108

91-21-11
Section W3340
Page 3 End
Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W3377	286A3377	AUTOPILOT E1-1 ELEV AND RUD PCU A SYSTEM - A													
0001	20	GA	130-7	22-12-31	D04079P	A06			D01681	1				YC051-YC052	
0001	20	PA	116-10	22-12-31	D04079P	A06			D43397P	1				YC053-YL999, YR301-YR328	
0001	20	PA	97-6	22-12-31	D04079P	A06			D43397P	1				YN231-YN236, YN501	
0002	20	GA	2-8	22-12-31	D01681	2			GD00949	DC..	E			YC051-YC052	
0006	22	GA	0-7	22-12-31	D01681	7			D01681	6				YC051-YC052	
0010	20	PA	116-10	SPARE	D04079P	B01			D43397P	46				YC053-YL999, YR301-YR328	
0010	20	PA	97-6	SPARE	D04079P	B01			D43397P	46				YN231-YN236, YN501	
0011	20	CQ	128-7	22-11-12	D04079P	A01			D01861	1				YC051-YC052	
0011	20	CQ	116-10	22-11-12	D04079P	A01			D43397P	32				YC053-YL999, YR301-YR328	
0011	20	CQ	97-6	22-11-12	D04079P	A01			D43397P	32				YN231-YN236, YN501	
0012	20	CQ	128-7	22-11-12	D04079P	A02			D01861	2				YC051-YC052	
0012	20	CQ	116-10	22-11-12	D04079P	A02			D43397P	33				YC053-YL999, YR301-YR328	
0012	20	CQ	97-6	22-11-12	D04079P	A02			D43397P	33				YN231-YN236, YN501	
0021	20	GA	130-7	22-12-31	D04079P	A05			D01681	21				YC051-YC052	
0021	20	PA	116-10	22-12-31	D04079P	A05			D43397P	34				YC053-YL999, YR301-YR328	
0021	20	PA	97-6	22-12-31	D04079P	A05			D43397P	34				YN231-YN236, YN501	
0022	20	GA	2-8	22-12-31	D01681	22			GD00949	DC..	E			YC051-YC052	
0101	20	GA	116-8	22-23-11	D40025P	A01			D43387J	8				YC051-YC052	
0101	20	PA	113-4	22-23-11	D40025P	A01			D43397P	35				YC053-YL999, YR301-YR328	
0101	20	PA	94-0	22-23-11	D40025P	A01			D43397P	35				YN231-YN236, YN501	
0102	20	GA	10-5	22-23-11	D43387J	9			GD11104	DC..	1			YC051-YC052	
1009	20	X1	7-1	22-23-11	D43397P	48			GD11104	DC..	1			YC053-YL999, YR301-YR328	
1009	20	X1	7-2	22-23-11	D43397P	48			GD11104	DC..	1			YN231-YN236, YN501	
1009Z			0-0	22-23-11	D43397P	S/R			GD11104	DC..	1			YC053-YN236, YN501-YR328	
2001B	22	GB	18-5	22-12-31	D01829	1			SM00003	9				YC051-YC052	
2001B	22	PB	3-9	22-12-31	D43397P	4			SM00003	9				YC053-YL999, YR301-YR328	
2001B	22	PB	3-8	22-12-31	D43397P	4			SM00003	9				YN231-YN236, YN501	
2001R	22	GB	0-0	22-12-31	D01829	2			SM00001	9				YC051-YC052	
2001R	22	PB	0-0	22-12-31	D43397P	3			SM00001	9				YC053-YN236, YN501-YR328	

WIRE LIST

D280A108

91-21-11

Section W3370

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3377	286A3377				AUTOPILOT E1-1 ELEV AND RUD PCU A SYSTEM - A (continued)										
2002B	22	GB	AB		113-8	22-12-31	D04079P	A20			SM00003		9		YC051-YC052
2002B	22	PB	AB		113-8	22-12-31	D04079P	A20			SM00003		9		YC053-YL999, YR301-YR328
2002B	22	PB	AB		94-4	22-12-31	D04079P	A20			SM00003		9		YN231-YN236, YN501
2002R	22	GB	AB		0-0	22-12-31	D04079P	A19			SM00001		9		YC051-YC052
2002R	22	PB	AB		0-0	22-12-31	D04079P	A19			SM00001		9		YC053-YN236, YN501-YR328
2003B	22	GB	AC		18-2	22-12-31	D02205	1			SM00003		9		YC051-YC052
2003B	22	PB	AC		3-9	22-12-31	D43397P	8			SM00003		9		YC053-YL999, YR301-YR328
2003B	22	PB	AC		3-8	22-12-31	D43397P	8			SM00003		9		YN231-YN236, YN501
2003R	22	GB	AC		0-0	22-12-31	D02205	2			SM00001		9		YC051-YC052
2003R	22	PB	AC		0-0	22-12-31	D43397P	7			SM00001		9		YC053-YN236, YN501-YR328
2004B	22	GB	AD		18-5	22-12-31	D01711	1			SM00003		9		YC051-YC052
2004B	22	PB	AD		3-9	22-12-31	D43397P	6			SM00003		9		YC053-YL999, YR301-YR328
2004B	22	PB	AD		3-8	22-12-31	D43397P	6			SM00003		9		YN231-YN236, YN501
2004R	22	GB	AD		0-0	22-12-31	D01711	2			SM00001		9		YC051-YC052
2004R	22	PB	AD		0-0	22-12-31	D43397P	5			SM00001		9		YC053-YN236, YN501-YR328
2005B	22	GB	AE		130-9	22-12-31	D04079P	B03			D02205		4		YC051-YC052
2005B	22	PB	AE		116-10	22-12-31	D04079P	B03			D43397P		10		YC053-YL999, YR301-YR328
2005B	22	PB	AE		97-6	22-12-31	D04079P	B03			D43397P		10		YN231-YN236, YN501
2005R	22	GB	AE		0-0	22-12-31	D04079P	B02			D02205		5		YC051-YC052
2005R	22	PB	AE		0-0	22-12-31	D04079P	B02			D43397P		9		YC053-YN236, YN501-YR328
2006B	22	GB	AF		18-0	22-12-31	D01681	9			SM00003		9		YC051-YC052
2006B	22	PB	AF		3-9	22-12-31	D43397P	12			SM00003		9		YC053-YL999, YR301-YR328
2006B	22	PB	AF		3-8	22-12-31	D43397P	12			SM00003		9		YN231-YN236, YN501
2006R	22	GB	AF		0-0	22-12-31	D01681	10			SM00001		9		YC051-YC052
2006R	22	PB	AF		0-0	22-12-31	D43397P	11			SM00001		9		YC053-YN236, YN501-YR328
2007B	22	GB	AG		130-7	22-12-31	D04079P	A08			D01681		5		YC051-YC052
2007B	22	PB	AG		116-10	22-12-31	D04079P	A08			D43397P		14		YC053-YL999, YR301-YR328
2007B	22	PB	AG		97-6	22-12-31	D04079P	A08			D43397P		14		YN231-YN236, YN501

WIRE LIST

D280A108

91-21-11

Section W3370

Page 2

Nov 12/2012



WIRE LIST
D280A108

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3377	286A3377			AUTOPILOT E1-1 ELEV AND RUD PCU A SYSTEM - A (continued)											
3001B	22	PC	CA		97-6	22-12-31	D04079P	A13			D43397P	16			YN231-YN236, YN501
3001R	22	GC	CA		0-0	22-12-31	D04079P	A12			D01681	11			YC051-YC052
3001R	22	PC	CA		0-0	22-12-31	D04079P	A12			D43397P	15			YC053-YN236, YN501-YR328
3001Y	22	GC	CA		0-0	22-12-31	D04079P	A14			D01681	13			YC051-YC052
3001Y	22	PC	CA		0-0	22-12-31	D04079P	A14			D43397P	17			YC053-YN236, YN501-YR328
3002B	22	GC	CB		131-0	22-12-31	D04079P	A10			D01829	4			YC051-YC052
3002B	22	PC	CB		116-10	22-12-31	D04079P	A10			D43397P	19			YC053-YL999, YR301-YR314
3002B	22	PC	CB		97-6	22-12-31	D04079P	A10			D43397P	19			YN231-YN236, YN501
3002B	22	PB	CB		116-10	22-12-31	D04079P	A10			D43397P	19			YR315-YR328
3002R	22	GC	CB		0-0	22-12-31	D04079P	A09			D01829	5			YC051-YC052
3002R	22	PC	CB		0-0	22-12-31	D04079P	A09			D43397P	18			YC053-YN236, YN501-YR314
3002R	22	PB	CB		0-0	22-12-31	D04079P	A09			D43397P	18			YR315-YR328
3002Y	22	GC	CB		0-0	22-12-31	D04079P	A11			D01829	3			YC051-YC052
3002Y	22	PC	CB		0-0	22-12-31	D04079P	A11			D43397P	20			YC053-YN236, YN501-YR314
3003B	22	GC	CC		131-0	22-12-31	D04079P	A17			D01711	5			YC051-YC052
3003B	22	PC	CC		116-10	22-12-31	D04079P	A17			D43397P	22			YC053-YL999, YR301-YR328
3003B	22	PC	CC		97-6	22-12-31	D04079P	A17			D43397P	22			YN231-YN236, YN501
3003R	22	GC	CC		0-0	22-12-31	D04079P	A16			D01711	4			YC051-YC052
3003R	22	PC	CC		0-0	22-12-31	D04079P	A16			D43397P	21			YC053-YN236, YN501-YR328
3003Y	22	GC	CC		0-0	22-12-31	D04079P	A18			D01711	3			YC051-YC052
3003Y	22	PC	CC		0-0	22-12-31	D04079P	A18			D43397P	23			YC053-YN236, YN501-YR328
3005B	22	N3	CE		116-8	22-23-12	D40025P	B02			D43387J	2			YC051-YC052
3005B	22	X3	CE		113-4	22-23-12	D40025P	B02			D43397P	29			YC053-YL999, YR301-YR328
3005B	22	X3	CE		94-0	22-23-12	D40025P	B02			D43397P	29			YN231-YN236, YN501
3005R	22	N3	CE		0-0	22-23-12	D40025P	B01			D43387J	1			YC051-YC052
3005R	22	X3	CE		0-0	22-23-12	D40025P	B01			D43397P	28			YC053-YN236, YN501-YR328
3005Y	22	N3	CE		0-0	22-23-12	D40025P	B03			D43387J	3			YC051-YC052
3005Y	22	X3	CE		0-0	22-23-12	D40025P	B03			D43397P	30			YC053-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W3370

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3377		286A3377			AUTOPILOT E1-1 ELEV AND RUD PCU A SYSTEM - A (continued)											
3005Z					CE	0-0	22-23-12	D40025P	PERG	1F		D43387J	S/R			YC051-YC052
3005Z					CE	0-0	22-23-12	D40025P	PERG	1F		D43397P	S/R			YC053-YN236, YN501-YR328
3006B		22	GC	CF		130-7	SPARE	D04079P	B08			D01681	REF	VP		YC051-YC052
3006B		22	PC	CF		116-10	SPARE	D04079P	B08			D43397P	41			YC053-YL999, YR301-YR328
3006B		22	PC	CF		97-6	SPARE	D04079P	B08			D43397P	41			YN231-YN236, YN501
3006R		22	GC	CF		0-0	SPARE	D04079P	B07			D01681	REF	VP		YC051-YC052
3006R		22	PC	CF		0-0	SPARE	D04079P	B07			D43397P	40			YC053-YN236, YN501-YR328
3006Y		22	GC	CF		0-0	SPARE	D04079P	B09			D01681	REF	VP		YC051-YC052
3006Y		22	PC	CF		0-0	SPARE	D04079P	B09			D43397P	42			YC053-YN236, YN501-YR328
YAAA						0-0	27-32-31	GD04803	ST..	E		D11409	S/R			YC051-YC052
W3379		286A3379			AUTOPILOT E1-4 ELEV AND RUD PCU A SYSTEM - B											
0001		20	GA			130-11	22-12-41	D04081J	6			D01687	1			YC051-YC052
0001		20	PA			118-5	22-12-41	D04081J	6			D43399P	1			YC053-YC055
0001		20	PA			118-11	22-12-41	D04081J	6			D43399P	1			YC056-YL999, YR301-YR328
0001		20	PA			99-6	22-12-41	D04081J	6			D43399P	1			YN231-YN236, YN501
0002		20	GA			2-10	22-12-41	D01687	2			GD00973	DC..	E		YC051-YC052
0002		20	CQ			110-4	SPARE	D40029P	A09			D43399P	2			YC053-YC055
0002		20	CQ			110-5	SPARE	D40029P	A09			D43399P	2			YC056-YL999, YR301-YR328
0002		20	CQ			91-1	SPARE	D40029P	A09			D43399P	2			YN231-YN236, YN501
0003		20	CQ			114-3	27-24-11	D40029P	A01			D43389J	8			YC051-YC052
0003		20	CQ			110-4	27-24-11	D40029P	A01			D43399P	35			YC053-YC055
0003		20	CQ			110-5	27-24-11	D40029P	A01			D43399P	35			YC056-YL999, YR301-YR328
0003		20	CQ			91-1	27-24-11	D40029P	A01			D43399P	35			YN231-YN236, YN501
0006		22	GA			0-7	22-12-41	D01687	6			D01687	7			YC051-YC052
0011		20	CQ			129-10	22-11-12	D04081J	1			D01857	1			YC051-YC052
0011		20	CQ			118-5	22-11-12	D04081J	1			D43399P	32			YC053-YC055
0011		20	CQ			118-11	22-11-12	D04081J	1			D43399P	32			YC056-YL999, YR301-YR328
0011		20	CQ			99-6	22-11-12	D04081J	1			D43399P	32			YN231-YN236, YN501
0012		20	CQ			129-10	22-11-12	D04081J	2			D01857	2			YC051-YC052
0012		20	CQ			118-5	22-11-12	D04081J	2			D43399P	33			YC053-YC055

WIRE LIST

D280A108

91-21-11

Section W3370

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3379	286A3379				AUTOPILOT E1-4 ELEV AND RUD PCU A SYSTEM - B (continued)											
0012	20		CQ		118-11		22-11-12	D04081J		2		D43399P		33		YC056-YL999, YR301-YR328
0012	20		CQ		99-6		22-11-12	D04081J		2		D43399P		33		YN231-YN236, YN501
0021	20		GA		130-11		22-12-41	D04081J		5		D01687		21		YC051-YC052
0021	20		PA		118-5		22-12-41	D04081J		5		D43399P		34		YC053-YC055
0021	20		PA		118-11		22-12-41	D04081J		5		D43399P		34		YC056-YL999, YR301-YR328
0021	20		PA		99-6		22-12-41	D04081J		5		D43399P		34		YN231-YN236, YN501
0022	20		GA		2-10		22-12-41	D01687		22		GD00973	DC..	E		YC051-YC052
0022	20		CQ		118-5		SPARE	D04081J		3		D43399P		50		YC053-YC055
0022	20		CQ		118-11		SPARE	D04081J		3		D43399P		50		YC056-YL999, YR301-YR328
0022	20		CQ		99-6		SPARE	D04081J		3		D43399P		50		YN231-YN236, YN501
0102	20		CQ		11-10		27-24-11	D43389J		9		GD11104	DC..	1		YC051-YC052
1009	20		X1	I	7-11		27-24-11	D43399P		48		GD11104	DC..	1		YC053-YN236, YN501-YR328
1009Z				I	0-0		27-24-11	D43399P		S/R		GD11104	DC..	1		YC053-YN236, YN501-YR328
2001B	22		GB	AA	5-5		22-12-41	D01677		1		SM00003		9		YC051-YC052
2001B	22		PB	AA	4-4		22-12-41	D43399P		4		SM00003		9		YC053-YC055
2001B	22		PB	AA	4-5		22-12-41	D43399P		4		SM00003		9		YC056-YN236, YN501-YR328
2001R	22		GB	AA	0-0		22-12-41	D01677		2		SM00001		9		YC051-YC052
2001R	22		PB	AA	0-0		22-12-41	D43399P		3		SM00001		9		YC053-YN236, YN501-YR328
2002B	22		GB	AB	128-5		22-12-41	D04081J		20		SM00003		9		YC051-YC052
2002B	22		PB	AB	114-7		22-12-41	D04081J		20		SM00003		9		YC053-YC055
2002B	22		PB	AB	115-1		22-12-41	D04081J		20		SM00003		9		YC056-YL999, YR301-YR328
2002B	22		PB	AB	95-8		22-12-41	D04081J		20		SM00003		9		YN231-YN236, YN501
2002R	22		GB	AB	0-0		22-12-41	D04081J		19		SM00001		9		YC051-YC052
2002R	22		PB	AB	0-0		22-12-41	D04081J		19		SM00001		9		YC053-YN236, YN501-YR328
2003B	22		GB	AC	6-8		22-12-41	D02207		1		SM00003		9		YC051-YC052
2003B	22		PB	AC	4-4		22-12-41	D43399P		8		SM00003		9		YC053-YC055
2003B	22		PB	AC	4-5		22-12-41	D43399P		8		SM00003		9		YC056-YN236, YN501-YR328
2003R	22		GB	AC	0-0		22-12-41	D02207		2		SM00001		9		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W3370

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W3379	286A3379			AUTOPILOT E1-4 ELEV AND RUD PCU A SYSTEM - B (continued)										
2003R	22	PB	AC	0-0	22-12-41	D43399P	7			SM00001		9		YC053-YN236, YN501-YR328
2004B	22	GB	AD	5-4	22-12-41	D01679	1			SM00003		9		YC051-YC052
2004B	22	PB	AD	4-4	22-12-41	D43399P	6			SM00003		9		YC053-YC055
2004B	22	PB	AD	4-5	22-12-41	D43399P	6			SM00003		9		YC056-YN236, YN501-YR328
2004R	22	GB	AD	0-0	22-12-41	D01679	2			SM00001		9		YC051-YC052
2004R	22	PB	AD	0-0	22-12-41	D43399P	5			SM00001		9		YC053-YN236, YN501-YR328
2005B	20	GB	AE	134-1	22-12-41	D04081J	23			D02207		5		YC051-YC052
2005B	20	PB	AE	118-5	22-12-41	D04081J	23			D43399P		10		YC053-YC055
2005B	20	PB	AE	118-11	22-12-41	D04081J	23			D43399P		10		YC056-YL999, YR301-YR328
2005B	20	PB	AE	99-6	22-12-41	D04081J	23			D43399P		10		YN231-YN236, YN501
2005R	20	GB	AE	0-0	22-12-41	D04081J	22			D02207		4		YC051-YC052
2005R	20	PB	AE	0-0	22-12-41	D04081J	22			D43399P		9		YC053-YN236, YN501-YR328
2006B	22	GB	AF	3-11	22-12-41	D01687	9			SM00003		9		YC051-YC052
2006B	22	PB	AF	4-4	22-12-41	D43399P	12			SM00003		9		YC053-YC055
2006B	22	PB	AF	4-5	22-12-41	D43399P	12			SM00003		9		YC056-YN236, YN501-YR328
2006R	22	GB	AF	0-0	22-12-41	D01687	10			SM00001		9		YC051-YC052
2006R	22	PB	AF	0-0	22-12-41	D43399P	11			SM00001		9		YC053-YN236, YN501-YR328
2007B	22	GB	AG	130-11	22-12-41	D04081J	8			D01687		5		YC051-YC052
2007B	22	PB	AG	118-5	22-12-41	D04081J	8			D43399P		14		YC053-YC055
2007B	22	PB	AG	118-11	22-12-41	D04081J	8			D43399P		14		YC056-YL999, YR301-YR328
2007B	22	PB	AG	99-6	22-12-41	D04081J	8			D43399P		14		YN231-YN236, YN501
2007R	22	GB	AG	0-0	22-12-41	D04081J	7			D01687		8		YC051-YC052
2007R	22	PB	AG	0-0	22-12-41	D04081J	7			D43399P		13		YC053-YN236, YN501-YR328
2008B	22	N2	AH	114-3	27-24-11	D40029P	A03			D43389J		5		YC051-YC052
2008B	22	X2	AH	110-4	27-24-11	D40029P	A03			D43399P		27		YC053-YC055
2008B	22	X2	AH	110-5	27-24-11	D40029P	A03			D43399P		27		YC056-YL999, YR301-YR328
2008B	22	X2	AH	91-1	27-24-11	D40029P	A03			D43399P		27		YN231-YN236, YN501
2008R	22	N2	AH	0-0	27-24-11	D40029P	A02			D43389J		4		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W3370

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3379	286A3379			AUTOPILOT E1-4 ELEV AND RUD PCU A SYSTEM - B (continued)											
2008R	22	X2		AH	0-0	27-24-11	D40029P	A02			D43399P	26			YC053-YN236, YN501-YR328
2008Z				AH	0-0	27-24-11	D40029P	PERG	1F		D43389J	S/R			YC051-YC052
2008Z				AH	0-0	27-24-11	D40029P	PERG	1F		D43399P	S/R			YC053-YN236, YN501-YR328
2009B	20	N2		AI	114-3	27-24-11	D40029P	A08			D43389J	7			YC051-YC052
2009B	20	X2		AI	110-4	27-24-11	D40029P	A08			D43399P	25			YC053-YC055
2009B	20	X2		AI	110-5	27-24-11	D40029P	A08			D43399P	25			YC056-YL999, YR301-YR328
2009B	20	X2		AI	91-1	27-24-11	D40029P	A08			D43399P	25			YN231-YN236, YN501
2009R	20	N2		AI	0-0	27-24-11	D40029P	A07			D43389J	6			YC051-YC052
2009R	20	X2		AI	0-0	27-24-11	D40029P	A07			D43399P	24			YC053-YN236, YN501-YR328
2009Z				AI	0-0	27-24-11	D40029P	PERG	1F		D43389J	S/R			YC051-YC052
2009Z				AI	0-0	27-24-11	D40029P	PERG	1F		D43399P	S/R			YC053-YN236, YN501-YR328
2010B	22	X2		AJ	110-4	SPARE	D40029P	B02			D43399P	37			YC053-YC055
2010B	22	X2		AJ	110-5	SPARE	D40029P	B02			D43399P	37			YC056-YL999, YR301-YR328
2010B	22	X2		AJ	91-1	SPARE	D40029P	B02			D43399P	37			YN231-YN236, YN501
2010R	22	X2		AJ	0-0	SPARE	D40029P	B01			D43399P	36			YC053-YN236, YN501-YR328
2010Z				AJ	0-0	SPARE	D40029P	PERG	1F		D43399P	S/R			YC053-YN236, YN501-YR328
2011B	20	HF		AL	125-0	27-32-31	D40029P	B07			D11409	4			YC051-YC052
2011B	20	N2		AK	112-0	27-32-31	D40029P	B07			D43399P	52			YC053-YC055
2011B	20	X2		AK	112-0	27-32-31	D40029P	B07			D43399P	52			YC056-YC057
2011B	20	X2		AK	110-5	27-32-31	D40029P	B07			D43399P	52			YC058-YL999, YR301-YR328
2011B	20	X2		AL	91-1	27-32-31	D40029P	B07			D43399P	52			YN231-YN236, YN501
2011R	20	HF		AL	0-0	27-32-31	D40029P	B06			D11409	3			YC051-YC052
2011R	20	N2		AK	0-0	27-32-31	D40029P	B06			D43399P	51			YC053-YC055
2011R	20	X2		AK	0-0	27-32-31	D40029P	B06			D43399P	51			YC056-YL999, YR301-YR328
2011R	20	X2		AL	0-0	27-32-31	D40029P	B06			D43399P	51			YN231-YN236, YN501
2011Z				AL	0-0	27-32-31	D40029P	PERG	1F		D11409	S/R			YC051-YC052
2011Z				AK	0-0	27-32-31	D40029P	PERG	1F		D43399P	S/R			YC053-YL999, YR301-YR328
2011Z				AL	0-0	27-32-31	D40029P	PERG	1F		D43399P	S/R			YN231-YN236, YN501

WIRE LIST

D280A108

91-21-11

Section W3370

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3379	286A3379			AUTOPILOT E1-4 ELEV AND RUD PCU A SYSTEM - B (continued)											
3001B	22	GC	CA	130-11	22-12-41	D04081J		13			D01687	12			YC051-YC052
3001B	22	PC	CA	118-5	22-12-41	D04081J		13			D43399P	16			YC053-YC055
3001B	22	PC	CA	118-11	22-12-41	D04081J		13			D43399P	16			YC056-YL999, YR301-YR328
3001B	22	PC	CA	99-6	22-12-41	D04081J		13			D43399P	16			YN231-YN236, YN501
3001R	22	GC	CA	0-0	22-12-41	D04081J		12			D01687	11			YC051-YC052
3001R	22	PC	CA	0-0	22-12-41	D04081J		12			D43399P	15			YC053-YN236, YN501-YR328
3001Y	22	GC	CA	0-0	22-12-41	D04081J		14			D01687	13			YC051-YC052
3001Y	22	PC	CA	0-0	22-12-41	D04081J		14			D43399P	17			YC053-YN236, YN501-YR328
3002B	22	GC	CB	133-4	22-12-41	D04081J		10			D01677	4			YC051-YC052
3002B	22	PC	CB	118-5	22-12-41	D04081J		10			D43399P	19			YC053-YC055
3002B	22	PC	CB	118-11	22-12-41	D04081J		10			D43399P	19			YC056-YL999, YR301-YR314
3002B	22	PC	CB	99-6	22-12-41	D04081J		10			D43399P	19			YN231-YN236, YN501
3002B	22	PB	CB	118-11	22-12-41	D04081J		10			D43399P	19			YR315-YR328
3002R	22	GC	CB	0-0	22-12-41	D04081J		9			D01677	5			YC051-YC052
3002R	22	PC	CB	0-0	22-12-41	D04081J		9			D43399P	18			YC053-YN236, YN501-YR314
3002R	22	PB	CB	0-0	22-12-41	D04081J		9			D43399P	18			YR315-YR328
3002Y	22	GC	CB	0-0	22-12-41	D04081J		11			D01677	3			YC051-YC052
3002Y	22	PC	CB	0-0	22-12-41	D04081J		11			D43399P	20			YC053-YN236, YN501-YR314
3003B	22	GC	CC	133-3	22-12-41	D04081J		17			D01679	5			YC051-YC052
3003B	22	PC	CC	118-5	22-12-41	D04081J		17			D43399P	22			YC053-YC055
3003B	22	PC	CC	118-11	22-12-41	D04081J		17			D43399P	22			YC056-YL999, YR301-YR328
3003B	22	PC	CC	99-6	22-12-41	D04081J		17			D43399P	22			YN231-YN236, YN501
3003R	22	GC	CC	0-0	22-12-41	D04081J		16			D01679	4			YC051-YC052
3003R	22	PC	CC	0-0	22-12-41	D04081J		16			D43399P	21			YC053-YN236, YN501-YR328
3003Y	22	GC	CC	0-0	22-12-41	D04081J		18			D01679	3			YC051-YC052
3003Y	22	PC	CC	0-0	22-12-41	D04081J		18			D43399P	23			YC053-YN236, YN501-YR328
3005B	22	N3	CE	114-3	27-24-11	D40029P		A05			D43389J	2			YC051-YC052
3005B	22	X3	CE	110-4	27-24-11	D40029P		A05			D43399P	29			YC053-YC055
3005B	22	X3	CE	110-5	27-24-11	D40029P		A05			D43399P	29			YC056-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3370

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3379	286A3379				AUTOPILOT E1-4 ELEV AND RUD PCU A SYSTEM - B (continued)										
3005B	22	X3	CE		91-1	27-24-11	D40029P	A05			D43399P	29			YN231-YN236, YN501
3005R	22	N3	CE		0-0	27-24-11	D40029P	A04			D43389J	1			YC051-YC052
3005R	22	X3	CE		0-0	27-24-11	D40029P	A04			D43399P	28			YC053-YN236, YN501-YR328
3005Y	22	N3	CE		0-0	27-24-11	D40029P	A06			D43389J	3			YC051-YC052
3005Y	22	X3	CE		0-0	27-24-11	D40029P	A06			D43399P	30			YC053-YN236, YN501-YR328
3005Z			CE		0-0	27-24-11	D40029P	PERG	1F		D43389J	S/R			YC051-YC052
3005Z			CE		0-0	27-24-11	D40029P	PERG	1F		D43399P	S/R			YC053-YN236, YN501-YR328
3006B	22	GC	CF		130-11	SPARE	D04081J		28		D01687	REF	VP		YC051-YC052
3006B	22	PC	CF		118-5	SPARE	D04081J		28		D43399P	41			YC053-YC055
3006B	22	PC	CF		118-11	SPARE	D04081J		28		D43399P	41			YC056-YL999, YR301-YR328
3006B	22	PC	CF		99-6	SPARE	D04081J		28		D43399P	41			YN231-YN236, YN501
3006R	22	GC	CF		0-0	SPARE	D04081J		27		D01687	REF	VP		YC051-YC052
3006R	22	PC	CF		0-0	SPARE	D04081J		27		D43399P	40			YC053-YN236, YN501-YR328
3006Y	22	GC	CF		0-0	SPARE	D04081J		29		D01687	REF	VP		YC051-YC052
3006Y	22	PC	CF		0-0	SPARE	D04081J		29		D43399P	42			YC053-YN236, YN501-YR328
3007B	22	X3	CG		110-4	SPARE	D40029P	B09			D43399P	44			YC053-YC055
3007B	22	X3	CG		110-5	SPARE	D40029P	B09			D43399P	44			YC056-YL999, YR301-YR328
3007B	22	X3	CG		91-1	SPARE	D40029P	B09			D43399P	44			YN231-YN236, YN501
3007R	22	X3	CG		0-0	SPARE	D40029P	B08			D43399P	43			YC053-YN236, YN501-YR328
3007Y	22	X3	CG		0-0	SPARE	D40029P	B10			D43399P	45			YC053-YN236, YN501-YR328
3007Z			CG		0-0	SPARE	D40029P	PERG	1F		D43399P	S/R			YC053-YN236, YN501-YR328
YAAA					0-0	27-32-31	GD04815	ST..	E		D11409	S/R			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W3370

Page 10 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W3381	286A3381				AUTOPILOT STAB TRIM CIRCUIT											
0004	20	HL		122-1	22-13-11	D04083P	A04				SP00117		9	YC051-YC052		
0004	20	PA		117-0	22-13-11	D04083P	A04				D44381P	4		YC053-YL999, YR301-YR328		
0004	20	PA		97-7	22-13-11	D04083P	A04				D44381P	4		YN231-YN501		
0005	20	HL		122-1	22-13-11	D04083P	A05				SP00113		9	YC051-YC052		
0005	20	PA		117-0	22-13-11	D04083P	A05				D44381P	5		YC053-YL999, YR301-YR328		
0005	20	PA		97-7	22-13-11	D04083P	A05				D44381P	5		YN231-YN501		
0006	20	PA		117-0	SPARE	D04083P	A02				D44381P	21		YC053-YD154		
0006	20	PA		117-0	SPARE	D04083P	A02				D44381P	1		YD155-YL999, YR301-YR328		
0006	20	PA		97-7	SPARE	D04083P	A02				D44381P	1		YN231-YN501		
0007	20	PA		117-0	SPARE	D04083P	A07				D44381P	25		YC053-YD154		
0007	20	PA		117-0	SPARE	D04083P	A07				D44381P	2		YD155-YL999, YR301-YR328		
0007	20	PA		97-7	SPARE	D04083P	A07				D44381P	2		YN231-YN501		
0009	16	HL		6-6	22-13-11	D00381	9				GD00046	AC..	1	YC051-YC052		
0010	20	HL		17-0	22-13-11	D00381	5				SP00115		9	YC051-YC052		
0012	20	HL		17-0	22-13-11	D00381	6				SP00119		9	YC051-YC052		
0013	16	HL		6-6	22-13-11	D00381	8				GD00046	AC..	1	YC051-YC052		
0014	20	HL		6-6	22-13-11	D00381	7				GD00046	DC..	1	YC051-YC052		
0015	20	HL		132-2	22-13-11	D00381	10				D04083P	A10		YC051-YC052		
0015	20	PA		117-0	22-13-11	D44381P	15				D04083P	A10		YC053-YL999, YR301-YR328		
0015	20	PA		97-7	22-13-11	D44381P	15				D04083P	A10		YN231-YN501		
0016	20	HL		132-2	22-13-11	D00381	4				D04083P	B03		YC051-YC052		
0016	20	PA		117-0	22-13-11	D44381P	16				D04083P	B03		YC053-YL999, YR301-YR328		
0016	20	PA		97-7	22-13-11	D44381P	16				D04083P	B03		YN231-YN501		
0017	20	HL		17-0	22-13-11	D00381	12				SP00506		9	YC051-YC052		
0018	20	HL		132-2	22-13-11	D00381	14				D04083P	B07		YC051-YC052		
0018	20	PA		117-0	22-13-11	D44381P	8				D04083P	B07		YC053-YD154		
0018	20	PA		117-0	22-13-11	D44381P	11				D04083P	B07		YD155-YL999, YR301-YR328		
0018	20	PA		97-7	22-13-11	D44381P	11				D04083P	B07		YN231-YN501		
0019	20	HL		132-2	22-13-11	D00381	13				D04083P	B04		YC051-YC052		
0019	20	PA		117-0	22-13-11	D44381P	9				D04083P	B04		YC053-YD154		
0019	20	PA		117-0	22-13-11	D44381P	12				D04083P	B04		YD155-YL999, YR301-YR328		

WIRE LIST

D280A108

91-21-11

Section W3380

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W3381	286A3381				AUTOPILOT STAB TRIM CIRCUIT (continued)											
0019	20		PA		97-7	22-13-11		D44381P	12			D04083P	B04			YN231-YN501
0020	20		PA		46-11	22-13-11		D44381P	10			SP00502		S		YC053-YD154
0020	20		PA		46-11	22-13-11		D44381P	13			SP00502		S		YD155-YL999, YR301-YR328
0020	20		PA		37-7	22-13-11		D44381P	13			SP00502		S		YN231-YN501
0023	22		G5		27-2	30-31-12		D40506P	B05			SP00875		9		YL968-YL999, YR301-YR328
0023	22		G5		27-1	30-31-12		D40506P	B05			SP00875		9		YN236-YN501
3001B	14		MZ	CA	119-2	22-13-11		D48901P	2			D00381	2	14		YC051-YC052
3001B	14		MZ	CA	104-0	22-13-11		D48901P	2			D44381P	23			YC053-YD154
3001B	14		MZ	CA	104-0	22-13-11		D48901P	2			D44381P	17	14		YD155-YL999, YR301-YR328
3001B	14		MZ	CA	84-7	22-13-11		D48901P	2			D44381P	17	14		YN231-YN501
3001R	14		MZ	CA	0-0	22-13-11		D48901P	1			D00381	1	14		YC051-YC052
3001R	14		MZ	CA	0-0	22-13-11		D48901P	1			D44381P	19			YC053-YD154
3001R	14		MZ	CA	0-0	22-13-11		D48901P	1			D44381P	9	14		YD155-YR328
3001Y	14		MZ	CA	0-0	22-13-11		D48901P	3			D00381	3	14		YC051-YC052
3001Y	14		MZ	CA	0-0	22-13-11		D48901P	3			D44381P	27			YC053-YD154
3001Y	14		MZ	CA	0-0	22-13-11		D48901P	3			D44381P	19	14		YD155-YR328
A-1					0-0	22-13-11		S00144	1			SP00113		9		YC051-YC052
A-2					0-0	22-13-11		S00144	2			S00144	CAP	Y		YC051-YC052
A-3					0-0	22-13-11		S00144	3			SP00115		9		YC051-YC052
A-4					0-0	27-41-12		S00144	4			SP00156		9		YC051-YC052
A-5					0-0	27-41-12		S00144	5			S00144	CAP	Y		YC051-YC052
A-6					0-0	27-41-12		S00144	6			SP00152		9		YC051-YC052
B-1					0-0	22-13-11		S00145	1			SP00117		9		YC051-YC052
B-2					0-0	22-13-11		S00145	2			S00145	CAP	Y		YC051-YC052
B-3					0-0	22-13-11		S00145	3			SP00119		9		YC051-YC052
W3387	286A3387				AUTOPILOT AB0180, PRESS. SEAL TO ELEV AND RUD PCU A SYSTEM - A											
0014	20		HA		3-0	22-23-11		GD00007	ST..	E		D00291	3			YC051-YD155
0014	20		HA		0-28	22-23-11		GD00007	ST..	E		D00291	3			YD157
0014	20		HA		0-28	22-23-12		GD00007	ST..	E		D00291	3			YD158, YL951-YR328
0015	20		HA		0-13	22-23-12		GD00007	ST..	E		SM00009		9		YC051-YD158, YL951-YR328
1001	20		HE	AC	13-5	22-23-11		D43387P	8			D00291	1			YC051-YC063
1001	20		HE	AC	13-11	22-23-11		D43387P	8			D00291	1			YC064-YC070
1001	20		HE	AC	12-10	22-23-11		D43387P	8			D00291	1			YD151-YD155
1001	20		HE	AC	12-7	22-23-11		D43387P	8			D00291	1			YD157-YD158

WIRE LIST

D280A108

91-21-11

Section W3380

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	
W3387	286A3387			AUTOPILOT AB0180, PRESS. SEAL TO ELEV AND RUD PCU A SYSTEM - A (continued)										
1001	20	HE	AC	12-8	22-23-11	D43387P	8			D00291	1		YL951-YR328	
1001Z			AC	0-0	22-23-11	D43387P	S/R			D00291	S/R		YC051-YD158, YL951-YR328	
1002	20	HE	AD	13-5	22-23-11	D43387P	9			D00291	2		YC051-YC063	
1002	20	HE	AD	13-11	22-23-11	D43387P	9			D00291	2		YC064-YC070	
1002	20	HE	AD	12-10	22-23-11	D43387P	9			D00291	2		YD151-YD155	
1002	20	HE	AD	12-7	22-23-11	D43387P	9			D00291	2		YD157-YD158	
1002	20	HE	AD	12-8	22-23-11	D43387P	9			D00291	2		YL951-YR328	
1002Z			AD	0-0	22-23-11	D43387P	S/R			D00291	S/R		YC051-YD158, YL951-YR328	
2001B	20	HF	AA	13-5	22-23-12	D43387P	5			D00291	9		YC051-YC063	
2001B	20	HF	AA	13-11	22-23-12	D43387P	5			D00291	9		YC064-YC070	
2001B	20	HF	AA	12-10	22-23-12	D43387P	5			D00291	9		YD151-YD155	
2001B	20	HF	AA	12-7	22-23-12	D43387P	5			D00291	9		YD157-YD158	
2001B	20	HF	AA	12-8	22-23-12	D43387P	5			D00291	9		YL951-YR328	
2001R	20	HF	AA	0-0	22-23-12	D43387P	4			D00291	10		YC051-YD158, YL951-YR328	
2001Z			AA	0-0	22-23-12	D43387P	S/R			D00291	S/R		YC051-YD158, YL951-YR328	
2002B	20	HF	AB	12-0	22-23-12	D43387P	7			SM00008	9		YC051-YC063	
2002B	20	HF	AB	12-6	22-23-12	D43387P	7			SM00008	9		YC064-YC070	
2002B	20	HF	AB	11-5	22-23-12	D43387P	7			SM00008	9		YD151-YD155	
2002B	20	HF	AB	11-2	22-23-12	D43387P	7			SM00008	9		YD157-YD158	
2002B	20	HF	AB	11-3	22-23-12	D43387P	7			SM00008	9		YL951-YR328	
2002R	20	HF	AB	0-0	22-23-12	D43387P	6			SM00005	9		YC051-YD158, YL951-YR328	
2002Z			AB	0-0	22-23-12	D43387P	S/R			SM00009	9		YC051-YD158, YL951-YR328	
3001B	20	HG	CA	13-5	22-23-12	D43387P	2			D00291	11		YC051-YC063	
3001B	20	HG	CA	13-11	22-23-12	D43387P	2			D00291	11		YC064-YC070	
3001B	20	HG	CA	12-10	22-23-12	D43387P	2			D00291	11		YD151-YD155	
3001B	20	HG	CA	12-7	22-23-12	D43387P	2			D00291	11		YD157-YD158	
3001B	20	HG	CA	12-8	22-23-12	D43387P	2			D00291	11		YL951-YR328	
3001R	20	HG	CA	0-0	22-23-12	D43387P	1			D00291	12		YC051-YD158, YL951-YR328	
3001Y	20	HG	CA	0-0	22-23-12	D43387P	3			D00291	4		YC051-YD158, YL951-YR328	
3001Z			CA	0-0	22-23-12	D43387P	S/R			D00291	S/R		YC051-YD158, YL951-YR328	

WIRE LIST

D280A108

91-21-11

Section W3380

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W3387	286A3387	AUTOPILOT AB0180, PRESS. SEAL TO ELEV AND RUD PCU A SYSTEM - A (continued)													
4521B	20	HS	HA	0-17	22-23-12	D00291		8	SM00008		9		YC051-YD158, YL951-YR328		
4521G	20	HS	HA	0-0	22-23-12	D00291		7	SM00005		9		YC051-YD158, YL951-YR328		
4521R	20	HS	HA	0-0	22-23-12	D00291		5	SM00005		9		YC051-YD158, YL951-YR328		
4521Y	20	HS	HA	0-0	22-23-12	D00291		6	SM00008		9		YC051-YD158, YL951-YR328		
4521Z			HA	0-0	22-23-12	D00291		S/R	SM00009		9		YC051-YD158, YL951-YR328		
W3389	286A3389	AUTOPILOT AB1080, PRESS. SEAL TO ELEV AND RUD PCU A SYSTEM - B													
0015	20	HA		0-15	27-24-11	GD00005	ST..	E	SM00009		9		YC051-YD158		
0015	20	HA		1-9	27-24-11	GD00005	ST..	E	SM00009		9		YL951-YR328		
1001	20	HE	AC	14-2	27-24-11	D43389P		8	D10013		1		YC051-YC063		
1001	20	HE	AC	14-9	27-24-11	D43389P		8	D10013		1		YC064-YC070		
1001	20	HE	AC	13-8	27-24-11	D43389P		8	D10013		1		YD151-YD155		
1001	20	HE	AC	13-3	27-24-11	D43389P		8	D10013		1		YD157-YD158		
1001	20	HE	AC	13-5	27-24-11	D43389P		8	D10013		1		YL951-YR328		
1001Z			AC	0-0	27-24-11	D43389P		S/R	D10013		S/R		YC051-YD158, YL951-YR328		
1002	20	HE	AD	14-2	27-24-11	D43389P		9	D10013		2		YC051-YC063		
1002	20	HE	AD	14-9	27-24-11	D43389P		9	D10013		2		YC064-YC070		
1002	20	HE	AD	13-8	27-24-11	D43389P		9	D10013		2		YD151-YD155		
1002	20	HE	AD	13-3	27-24-11	D43389P		9	D10013		2		YD157-YD158		
1002	20	HE	AD	13-5	27-24-11	D43389P		9	D10013		2		YL951-YR328		
1002Z			AD	0-0	27-24-11	D43389P		S/R	D10013		S/R		YC051-YD158, YL951-YR328		
2001B	20	HF	AA	12-1	27-24-11	D43389P		5	SM00008		9		YC051-YC063		
2001B	20	HF	AA	12-7	27-24-11	D43389P		5	SM00008		9		YC064-YC070		
2001B	20	HF	AA	11-6	27-24-11	D43389P		5	SM00008		9		YD151-YD155		
2001B	20	HF	AA	11-2	27-24-11	D43389P		5	SM00008		9		YD157-YD158		
2001B	20	HF	AA	11-3	27-24-11	D43389P		5	SM00008		9		YL951-YR328		
2001R	20	HF	AA	0-0	27-24-11	D43389P		4	SM00005		9		YC051-YD158, YL951-YR328		
2001Z			AA	0-0	27-24-11	D43389P		S/R	SM00009		9		YC051-YD158, YL951-YR328		
2002B	20	HF	AB	14-2	27-24-11	D43389P		7	D10013		9		YC051-YC063		
2002B	20	HF	AB	14-9	27-24-11	D43389P		7	D10013		9		YC064-YC070		

WIRE LIST

D280A108

91-21-11

Section W3380

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3389	286A3389			AUTOPILOT AB1080, PRESS. SEAL TO ELEV AND RUD PCU A SYSTEM - B (continued)											
2002B	20	HF	AB		13-8	27-24-11	D43389P		7		D10013		9		YD151-YD155
2002B	20	HF	AB		13-3	27-24-11	D43389P		7		D10013		9		YD157-YD158
2002B	20	HF	AB		13-5	27-24-11	D43389P		7		D10013		9		YL951-YR328
2002R	20	HF	AB		0-0	27-24-11	D43389P		6		D10013		10		YC051-YD158, YL951-YR328
2002Z				AB	0-0	27-24-11	D43389P		S/R		D10013		S/R		YC051-YD158, YL951-YR328
3001B	20	HG	CA		14-2	27-24-11	D43389P		2		D10013		11		YC051-YC063
3001B	20	HG	CA		14-9	27-24-11	D43389P		2		D10013		11		YC064-YC070
3001B	20	HG	CA		13-8	27-24-11	D43389P		2		D10013		11		YD151-YD155
3001B	20	HG	CA		13-3	27-24-11	D43389P		2		D10013		11		YD157-YD158
3001B	20	HG	CA		13-5	27-24-11	D43389P		2		D10013		11		YL951-YR328
3001R	20	HG	CA		0-0	27-24-11	D43389P		1		D10013		12		YC051-YD158, YL951-YR328
3001Y	20	HG	CA		0-0	27-24-11	D43389P		3		D10013		4		YC051-YD158, YL951-YR328
3001Z				CA	0-0	27-24-11	D43389P		S/R		D10013		S/R		YC051-YD158, YL951-YR328
4521B	20	HS	HA		0-25	27-24-11	D10013		8		SM00008		9		YC051-YD158
4521B	20	HS	HA		2-8	27-24-11	D10013		8		SM00008		9		YL951-YR328
4521G	20	HS	HA		0-0	27-24-11	D10013		7		SM00005		9		YC051-YD158, YL951-YR328
4521R	20	HS	HA		0-0	27-24-11	D10013		5		SM00005		9		YC051-YD158, YL951-YR328
4521Y	20	HS	HA		0-0	27-24-11	D10013		6		SM00008		9		YC051-YD158, YL951-YR328
4521Z				HA	0-0	27-24-11	D10013		S/R		SM00009		9		YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W3380

Page 5 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3391	286A3391				AUTOPILOT AB1050L, STAB TRIM CIRCUIT										
1004	20		X1	D	8-4	22-13-11	D44381J	4			SP00117		9		YC053-YD155, YL953-YL999, YN235-YR328
1004	20		X1	D	8-1	22-13-11	D44381J	4			SP00117		9		YD157-YL952, YN231-YN234
1004Z				D	0-0	22-13-11	D44381J	S/R			GD00078	ST..	1		YC053-YD153
1004Z				D	0-0	22-13-11	D44381J	S/R			GD00024	ST..	1		YD154-YR328
1005	20		X1	E	8-4	22-13-11	D44381J	5			SP00113		9		YC053-YD155, YL953-YL999, YN235-YR328
1005	20		X1	E	8-1	22-13-11	D44381J	5			SP00113		9		YD157-YL952, YN231-YN234
1005Z				E	0-0	22-13-11	D44381J	S/R			GD00078	ST..	1		YC053-YD153
1005Z				E	0-0	22-13-11	D44381J	S/R			GD00024	ST..	1		YD154-YR328
1009	16		X1	I	6-0	22-13-11	D00381	9			GD00045	AC..	1		YC053-YD153
1009	16		X1	I	6-2	22-13-11	D00381	9			GD00045	AC..	1		YD154-YR328
1009Z				I	0-0	22-13-11	D00381			AA	GD00045	ST..	1		YC053-YR328
1010	20		X1	J	17-5	22-13-11	D00381	5			SP00115		9		YC053-YD153
1010	20		X1	J	17-7	22-13-11	D00381	5			SP00115		9		YD154-YD155
1010	20		X1	J	17-6	22-13-11	D00381	5			SP00115		9		YD157-YR328
1010Z				J	0-0	22-13-11	D00381			AC	GD00078	ST..	1		YC053-YD153
1010Z				J	0-0	22-13-11	D00381			AC	GD00024	ST..	1		YD154-YR328
1012	20		X1	L	17-5	22-13-11	D00381	6			SP00119		9		YC053-YD153
1012	20		X1	L	17-7	22-13-11	D00381	6			SP00119		9		YD154-YD155
1012	20		X1	L	17-6	22-13-11	D00381	6			SP00119		9		YD157-YR328
1012Z				L	0-0	22-13-11	D00381			AC	GD00078	ST..	1		YC053-YD153
1012Z				L	0-0	22-13-11	D00381			AC	GD00024	ST..	1		YD154-YR328
1013	16		X1	M	6-0	22-13-11	D00381	8			GD00045	AC..	1		YC053-YD153
1013	16		X1	M	6-2	22-13-11	D00381	8			GD00045	AC..	1		YD154-YR328
1013Z				M	0-0	22-13-11	D00381			AA	GD00045	ST..	1		YC053-YR328
1014	20		X1	N	6-0	22-13-11	D00381	7			GD00045	AC..	1		YC053-YD153
1014	20		X1	N	6-2	22-13-11	D00381	7			GD00045	AC..	1		YD154-YR328
1014Z				N	0-0	22-13-11	D00381			AA	GD00045	ST..	1		YC053-YR328
1015	20		X1	O	15-9	22-13-11	D44381J	15			D00381		10		YC053-YD153
1015	20		X1	O	15-11	22-13-11	D44381J	15			D00381		10		YD154-YD155, YL953-YL999, YN235-YR328
1015	20		X1	O	15-8	22-13-11	D44381J	15			D00381		10		YD157-YL952, YN231-YN234

WIRE LIST

D280A108

91-21-11

Section W3390

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3391 286A3391 AUTOPILOT AB1050L, STAB TRIM CIRCUIT (continued)																
1015Z					O	0-0	22-13-11	D44381J	S/R			D00381			AB	YC053-YR328
1016	20	X1			P	15-9	22-13-11	D44381J	16			D00381	4			YC053-YD153
1016	20	X1			P	15-11	22-13-11	D44381J	16			D00381	4			YD154-YD155, YL953-YL999, YN235-YR328
1016	20	X1			P	15-8	22-13-11	D44381J	16			D00381	4			YD157-YL952, YN231-YN234
1016Z					P	0-0	22-13-11	D44381J	S/R			D00381			AB	YC053-YR328
1017	20	X1			Q	15-9	22-13-11	D00381	12			D44381J	10			YC053-YD153
1017	20	X1			Q	15-11	22-13-11	D00381	12			D44381J	10			YD154
1017	20	X1			Q	15-11	22-13-11	D00381	12			D44381J	13			YD155, YL953-YL999, YN235-YR328
1017	20	X1			Q	15-8	22-13-11	D00381	12			D44381J	13			YD157-YL952, YN231-YN234
1017Z					Q	0-0	22-13-11	D00381			AD	D44381J	S/R			YC053-YR328
1018	20	X1			R	15-9	22-13-11	D00381	14			D44381J	8			YC053-YD153
1018	20	X1			R	15-11	22-13-11	D00381	14			D44381J	8			YD154
1018	20	X1			R	15-11	22-13-11	D00381	14			D44381J	11			YD155
1018	20	X1			R	15-8	22-13-11	D00381	13			D44381J	11			YD157-YL952, YN231-YN234
1018	20	X1			R	15-11	22-13-11	D00381	13			D44381J	11			YL953-YL999, YN235-YR328
1018Z					R	0-0	22-13-11	D00381			AD	D44381J	S/R			YC053-YR328
1019	20	X1			S	15-9	22-13-11	D00381	13			D44381J	9			YC053-YD153
1019	20	X1			S	15-11	22-13-11	D00381	13			D44381J	9			YD154
1019	20	X1			S	15-11	22-13-11	D00381	13			D44381J	12			YD155
1019	20	X1			S	15-8	22-13-11	D00381	14			D44381J	12			YD157-YL952, YN231-YN234
1019	20	X1			S	15-11	22-13-11	D00381	14			D44381J	12			YL953-YL999, YN235-YR328
1019Z					S	0-0	22-13-11	D00381			AD	D44381J	S/R			YC053-YR328
3001B	14	MZ			CA	15-9	22-13-11	D44381J	23			D00381	2	14		YC053-YD153
3001B	14	MZ			CA	15-11	22-13-11	D44381J	23			D00381	2	14		YD154
3001B	14	MZ			CA	15-11	22-13-11	D44381J	17	14		D00381	2	14		YD155, YL953-YL999, YN235-YR328
3001B	14	MZ			CA	15-8	22-13-11	D44381J	17	14		D00381	2	14		YD157-YL952, YN231-YN234
3001R	14	MZ			CA	0-0	22-13-11	D44381J	19			D00381	1	14		YC053-YD154
3001R	14	MZ			CA	0-0	22-13-11	D44381J	9	14		D00381	1	14		YD155-YR328

WIRE LIST

D280A108

91-21-11

Section W3390

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3391	286A3391			AUTOPILOT AB1050L, STAB TRIM CIRCUIT (continued)											
3001Y	14	MZ	CA		0-0	22-13-11	D44381J	27			D00381	3	14		YC053-YD154
3001Y	14	MZ	CA		0-0	22-13-11	D44381J	19	14		D00381	3	14		YD155-YR328
A-1					0-0	22-13-11	S00144	1			SP00113		9		YC053-YR328
A-2					0-0	22-13-11	S00144	2			S00144	CAP	Y		YC053-YR328
A-3					0-0	22-13-11	S00144	3			SP00115		9		YC053-YR328
A-4					0-0	27-41-12	S00144	4			SP00156		9		YC053-YR328
A-5					0-0	27-41-12	S00144	5			S00144	CAP	Y		YC053-YR328
A-6					0-0	27-41-12	S00144	6			SP00152		9		YC053-YR328
B-1					0-0	22-13-11	S00145	1			SP00117		9		YC053-YR328
B-2					0-0	22-13-11	S00145	2			S00145	CAP	Y		YC053-YR328
B-3					0-0	22-13-11	S00145	3			SP00119		9		YC053-YR328
FRAA					0-0	22-13-11	D00381			AA	GD04801	ST..	E	*1	YC053-YR328
FRAB					0-0	22-13-11	D00381			AB	GD04801	ST..	E	*1	YC053-YR328
FRAC					0-0	22-13-11	D00381			AC	GD04801	ST..	E	*1	YC053-YR328
FRAD					0-0	22-13-11	D00381			AD	GD04801	ST..	E	*1	YC053-YR328
YAAA					0-0	22-13-11	D44381J		S/R		GD04801	ST..	E		YC053-YR328
W3393	286A3393			MACH TRIM SERVO, AB1050L TO STA 1156											
0011	20	PA			2-11	22-18-11	D00545	11			GD00479	DC..	E		YC053-YC064
0011	20	PA			3-2	22-18-11	D00545	11			GD00479	DC..	E		YC065-YL967, YN231-YN235
0011	20	PA			3-10	22-18-11	D00545	11			GD00479	DC..	E		YL968-YL999, YN236-YR328
0014	20	PA			2-11	22-18-11	D00545	14			GD00479	DC..	E		YC053-YC064
0014	20	PA			3-2	22-18-11	D00545	14			GD00479	DC..	E		YC065-YL967, YN231-YN235
0014	20	PA			3-10	22-18-11	D00545	14			GD00479	DC..	E		YL968-YL999, YN236-YR328
1013	20	VF	M		16-7	22-18-11	D00545	13			D43393J		13		YC053-YC064
1013	20	VF	M		16-6	22-18-11	D00545	13			D43393J		13		YC065-YR328
1013Z			M		0-0	22-18-11	GD04809		ST..	E	D43393J		S/R		YC053-YR328
1015	20	VF	O		16-7	SPARE	D43393J	15			D00545		15		YC053-YC064
1015	20	VF	O		16-6	SPARE	D43393J	15			D00545		15		YC065-YR328
1015Z			O		0-0	SPARE	D43393J		S/R		GD04809	ST..	E	*1	YC053-YR328
1017	20	VF	P		16-7	SPARE	D43393J	17			D00545		17		YC053-YC064
1017	20	VF	P		16-6	SPARE	D43393J	17			D00545		17		YC065-YR328
1017Z			P		0-0	SPARE	D43393J		S/R		GD04809	ST..	E	*1	YC053-YR328
1019	20	VF	R		16-7	SPARE	D43393J	19			D00545		19		YC053-YC064
1019	20	VF	R		16-6	SPARE	D43393J	19			D00545		19		YC065-YR328

WIRE LIST

D280A108

91-21-11

Section W3390

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3393		286A3393			MACH TRIM SERVO, AB1050L TO STA 1156 (continued)											
1019Z					R	0-0	SPARE	D43393J		S/R		GD04809	ST..	E	*1	YC053-YR328
1021		20		VF	T	16-7	SPARE	D43393J		21		D00545	21			YC053-YC064
1021		20		VF	T	16-6	SPARE	D43393J		21		D00545	21			YC065-YR328
1021Z					T	0-0	SPARE	D43393J		S/R		D00545	S/R			YC053-YR328
2001B		22		HF	AA	16-7	22-18-11	D43393J		2		D00545	1			YC053-YC064
2001B		22		HF	AA	16-6	22-18-11	D43393J		2		D00545	1			YC065-YR328
2001R		22		HF	AA	0-0	22-18-11	D43393J		1		D00545	2			YC053-YR328
2001Z					AA	0-0	22-18-11	D43393J		S/R		GD04809	ST..	E	*	YC053-YR328
2006B		22		HF	AF	16-7	22-18-11	D43393J		6		D00545	3			YC053-YC064
2006B		22		HF	AF	16-6	22-18-11	D43393J		6		D00545	3			YC065-YR328
2006R		22		HF	AF	0-0	22-18-11	D43393J		5		D00545	6			YC053-YR328
2006Z					AF	0-0	22-18-11	D43393J		S/R		GD04809	ST..	E	*	YC053-YR328
2024B		22		HF	AY	16-7	22-18-11	D43393J		4		D00545	23			YC053-YC064
2024B		22		HF	AY	16-6	22-18-11	D43393J		4		D00545	23			YC065-YR328
2024R		22		HF	AY	0-0	22-18-11	D43393J		3		D00545	24			YC053-YR328
2024Z					AY	0-0	22-18-11	D43393J		S/R		GD04809	ST..	E	*	YC053-YR328
2026B		22		HF	BA	16-7	22-18-11	D43393J		8		D00545	25			YC053-YC064
2026B		22		HF	BA	16-6	22-18-11	D43393J		8		D00545	25			YC065-YR328
2026R		22		HF	BA	0-0	22-18-11	D43393J		7		D00545	26			YC053-YR328
2026Z					BA	0-0	22-18-11	D43393J		S/R		GD04809	ST..	E	*	YC053-YR328
W3397		286A3397			AUTOPILOT AB1050L TO ELEV AND RUD PCU SYSTEM -A											
0002		20		GA		2-8	22-12-31	D01681		2		GD00949	DC..	E	*1	YC053-YC064
0002		20		PA		2-8	22-12-31	D01681		2		GD00949	DC..	E	*1	YC065-YD157
0002		20		PA		2-1	22-12-31	D01681		2		GD00949	DC..	E	*1	YD158-YN236, YN501-YR328
0006		22		GA		0-7	22-12-31	D01681		7		D01681	6			YC053-YC064
0006		22		PA		0-7	22-12-31	D01681		7		D01681	6			YC065-YN236, YN501-YR328
0022		20		GA		2-8	22-12-31	D01681		22		GD00949	DC..	E	*1	YC053-YC064
0022		20		PA		2-8	22-12-31	D01681		22		GD00949	DC..	E	*1	YC065-YD157
0022		20		PA		2-1	22-12-31	D01681		22		GD00949	DC..	E	*1	YD158-YN236, YN501-YR328
1001		20		HE	A	15-5	22-12-31	D43397J		1		D01681	1			YC053-YD157
1001		20		HE	A	14-1	22-12-31	D43397J		1		D01681	1			YD158-YN236, YN501-YR328
1001Z					A	0-0	22-12-31	D43397J		S/R		D01681			AA	YC053-YD153
1001Z					A	0-0	22-12-31	D43397J		S/R		GD00949	ST..	E	*2	YD154-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W3390

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3397	286A3397			AUTOPILOT AB1050L TO ELEV AND RUD PCU SYSTEM -A (continued)											
1002	20	HE	B		13-4	22-11-12	D43397J	32			D01861	1			YC053-YN236, YN501-YR328
1002Z			B		0-0	22-11-12	D43397J	S/R			GD00973	ST..	E	*1	YC053-YN236, YN501-YR328
1003	20	HE	C		13-4	22-11-12	D43397J	33			D01861	2			YC053-YN236, YN501-YR328
1003Z			C		0-0	22-11-12	D43397J	S/R			GD00973	ST..	E	*1	YC053-YN236, YN501-YR328
1004	20	HE	D		15-5	22-12-31	D43397J	34			D01681	21			YC053-YD157
1004	20	HE	D		14-1	22-12-31	D43397J	34			D01681	21			YD158-YN236, YN501-YR328
1004Z			D		0-0	22-12-31	D43397J	S/R			D01681			AA	YC053-YD153
1004Z			D		0-0	22-12-31	D43397J	S/R			GD00949	ST..	E	*	YD154-YN236, YN501-YR328
1005	20	HE	E		4-8	22-23-11	D43397J	35			D43387J	8			YC053-YN236, YN501-YR328
1005Z			E		0-0	22-23-11	D43397J	S/R			D43387J	S/R			YC053-YN236, YN501-YR328
1009	20	HE	I		4-8	22-23-11	D43387J	9			D43397J	48			YC053-YN236, YN501-YR328
1009Z			I		0-0	22-23-11	D43387J	S/R			D43397J	S/R			YC053-YN236, YN501-YR328
2001B	22	HF	AA		15-7	22-12-31	D01829	1			D43397J	4			YC053-YN236, YN501-YR328
2001R	22	HF	AA		0-0	22-12-31	D01829	2			D43397J	3			YC053-YN236, YN501-YR328
2001Z			AA		0-0	22-12-31	D01829	S/R			D43397J	S/R			YC053-YN236, YN501-YR328
2003B	22	HF	AC		15-7	22-12-31	D02205	1			D43397J	8			YC053-YD157
2003B	22	HF	AC		14-1	22-12-31	D02205	1			D43397J	8			YD158-YN236, YN501-YR328
2003R	22	HF	AC		0-0	22-12-31	D02205	2			D43397J	7			YC053-YN236, YN501-YR328
2003Z			AC		0-0	22-12-31	D02205	S/R			D43397J	S/R			YC053-YN236, YN501-YR328
2004B	22	HF	AD		15-10	22-12-31	D01711	1			D43397J	6			YC053-YN236, YN501-YR328
2004R	22	HF	AD		0-0	22-12-31	D01711	2			D43397J	5			YC053-YN236, YN501-YR328

WIRE LIST
D280A108

91-21-11
Section W3390
Page 5
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W3397	286A3397	AUTOPILOT AB1050L TO ELEV AND RUD PCU SYSTEM -A (continued)													
2004Z		AD	0-0	22-12-31	D01711	S/R			D43397J	S/R				YC053-YN236, YN501-YR328	
2005B	22	HF AE	15-7	22-12-31	D43397J	10			D02205	4				YC053-YD157	
2005B	22	HF AE	14-1	22-12-31	D43397J	10			D02205	4				YD158-YN236, YN501-YR328	
2005R	22	HF AE	0-0	22-12-31	D43397J	9			D02205	5				YC053-YN236, YN501-YR328	
2005Z		AE	0-0	22-12-31	D43397J	S/R			D02205	S/R				YC053-YN236, YN501-YR328	
2006B	22	HF AF	15-5	22-12-31	D01681	9			D43397J	12				YC053-YD157	
2006B	22	HF AF	14-1	22-12-31	D01681	9			D43397J	12				YD158-YN236, YN501-YR328	
2006R	22	HF AF	0-0	22-12-31	D01681	10			D43397J	11				YC053-YN236, YN501-YR328	
2006Z		AF	0-0	22-12-31	D01681				D43397J	S/R				YC053-YD153	
2006Z		AF	0-0	22-12-31	GD00949	ST..	E	AA *	D43397J	S/R				YD154-YN236, YN501-YR328	
2007B	22	HF AG	15-5	22-12-31	D43397J	14			D01681	5				YC053-YD157	
2007B	22	HF AG	14-1	22-12-31	D43397J	14			D01681	5				YD158-YN236, YN501-YR328	
2007R	22	HF AG	0-0	22-12-31	D43397J	13			D01681	8				YC053-YN236, YN501-YR328	
2007Z		AG	0-0	22-12-31	D43397J	S/R			D01681					YC053-YD153	
2007Z		AG	0-0	22-12-31	D43397J	S/R			GD00949	ST..	E	AA *		YD154-YN236, YN501-YR328	
2008B	22	N2 AH	4-8	22-23-12	D43397J	27			D43387J	7				YC053-YC064	
2008B	22	X2 AH	4-8	22-23-12	D43397J	27			D43387J	7				YC065-YN236, YN501-YR328	
2008R	22	N2 AH	0-0	22-23-12	D43397J	26			D43387J	6				YC053-YC064	
2008R	22	X2 AH	0-0	22-23-12	D43397J	26			D43387J	6				YC065-YN236, YN501-YR328	
2008Z		AH	0-0	22-23-12	D43397J	S/R			D43387J	S/R				YC053-YN236, YN501-YR328	
2009B	22	N2 AJ	4-8	22-23-12	D43397J	25			D43387J	5				YC053-YC064	
2009B	22	X2 AJ	4-8	22-23-12	D43397J	25			D43387J	5				YC065-YN236, YN501-YR328	
2009R	22	N2 AJ	0-0	22-23-12	D43397J	24			D43387J	4				YC053-YC064	
2009R	22	X2 AJ	0-0	22-23-12	D43397J	24			D43387J	4				YC065-YN236, YN501-YR328	

WIRE LIST

D280A108

91-21-11

Section W3390

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To							
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3397	286A3397			AUTOPILOT AB1050L TO ELEV AND RUD PCU SYSTEM -A (continued)											
2009Z				AJ	0-0	22-23-12	D43397J	S/R			D43387J	S/R			YC053-YN236, YN501-YR328
2012B	20	HF	AL		7-11	27-32-31	D43397J	51			D11409	2			YC053-YN236, YN501-YR328
2012R	20	HF	AL		0-0	27-32-31	D43397J	50			D11409	1			YC053-YN236, YN501-YR328
2012Z			AL		0-0	27-32-31	D43397J	S/R			D11409	S/R			YC053-YN236, YN501-YR328
3001B	22	HG	CA		15-5	22-12-31	D43397J	16			D01681	12			YC053-YD157
3001B	22	HG	CA		14-1	22-12-31	D43397J	16			D01681	12			YD158-YN236, YN501-YR328
3001R	22	HG	CA		0-0	22-12-31	D43397J	15			D01681	11			YC053-YN236, YN501-YR328
3001Y	22	HG	CA		0-0	22-12-31	D43397J	17			D01681	13			YC053-YN236, YN501-YR328
3001Z			CA		0-0	22-12-31	D43397J	S/R			D01681			AA	YC053-YD153
3001Z			CA		0-0	22-12-31	D43397J	S/R			GD00949	ST..	E	*2	YD154-YN236, YN501-YR328
3002B	22	HG	CB		15-7	22-12-31	D43397J	19			D01829	4			YC053-YN236, YN501-YR314
3002B	22	HF	CB		15-7	22-12-31	D43397J	19			D01829	4			YR315-YR328
3002R	22	HG	CB		0-0	22-12-31	D43397J	18			D01829	5			YC053-YN236, YN501-YR314
3002R	22	HF	CB		0-0	22-12-31	D43397J	18			D01829	5			YR315-YR328
3002Y	22	HG	CB		0-0	22-12-31	D43397J	20			D01829	3			YC053-YN236, YN501-YR314
3002Z			CB		0-0	22-12-31	D43397J	S/R			D01829	S/R			YC053-YN236, YN501-YR328
3003B	22	HG	CC		15-10	22-12-31	D43397J	22			D01711	5			YC053-YN236, YN501-YR328
3003R	22	HG	CC		0-0	22-12-31	D43397J	21			D01711	4			YC053-YN236, YN501-YR328
3003Y	22	HG	CC		0-0	22-12-31	D43397J	23			D01711	3			YC053-YN236, YN501-YR328
3003Z			CC		0-0	22-12-31	D43397J	S/R			D01711	S/R			YC053-YN236, YN501-YR328
3005B	22	N3	CE		4-8	22-23-12	D43397J	29			D43387J	2			YC053-YC064
3005B	22	X3	CE		4-8	22-23-12	D43397J	29			D43387J	2			YC065-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W3390

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3397	286A3397			AUTOPILOT AB1050L TO ELEV AND RUD PCU SYSTEM -A (continued)											
3005R	22	N3	CE		0-0	22-23-12	D43397J	28			D43387J	1			YC053-YC064
3005R	22	X3	CE		0-0	22-23-12	D43397J	28			D43387J	1			YC065-YN236, YN501-YR328
3005Y	22	N3	CE		0-0	22-23-12	D43397J	30			D43387J	3			YC053-YC064
3005Y	22	X3	CE		0-0	22-23-12	D43397J	30			D43387J	3			YC065-YN236, YN501-YR328
3005Z			CE		0-0	22-23-12	D43397J	S/R			D43387J	S/R			YC053-YN236, YN501-YR328
3006B	22	HG	CF		15-5	SPARE	D43397J	41			D01681	REF	VP		YC053-YD157
3006B	22	HG	CF		14-1	SPARE	D43397J	41			D01681	REF	VP		YD158-YN236, YN501-YR328
3006R	22	HG	CF		0-0	SPARE	D43397J	40			D01681	REF	VP		YC053-YN236, YN501-YR328
3006Y	22	HG	CF		0-0	SPARE	D43397J	42			D01681	REF	VP		YC053-YN236, YN501-YR328
3006Z			CF		0-0	SPARE	D43397J	S/R			D01681			AA	YC053-YD153
3006Z			CF		0-0	SPARE	D43397J	S/R			GD00949	ST..	E	*2	YD154-YN236, YN501-YR328
FRAA					0-0	22-12-31	GD00949	ST..	E		D01681			AA	YC053-YD153
W3399	286A3399			AUTOPILOT AB1050R ELEV AND STANDBY RUDDER PCU, SYSTEM - B											
0006	22	GA			0-7	22-12-41	D01687	6			D01687	7			YC053-YC064
0006	22	PA			0-7	22-12-41	D01687	6			D01687	7			YC065-YN236, YN501-YR328
1001	20	HE	A		14-0	22-12-41	D43399J	1			D01687	1			YC053-YN236, YN501-YR328
1001Z			A		0-0	22-12-41	D43399J	S/R			GD00973	ST..	E	*4	YC053-YN236, YN501-YR328
1002	20	HE	B		13-0	22-11-12	D43399J	32			D01857	1			YC053-YD153
1002	20	HE	B		13-5	22-11-12	D43399J	32			D01857	1			YD154-YN236, YN501-YR328
1002Z			B		0-0	22-11-12	D43399J	S/R			D01857	S/R			YC053-YN236, YN501-YR328
1003	20	HE	C		13-0	22-11-12	D43399J	33			D01857	2			YC053-YD153
1003	20	HE	C		13-5	22-11-12	D43399J	33			D01857	2			YD154-YN236, YN501-YR328
1003Z			C		0-0	22-11-12	D43399J	S/R			D01857	S/R			YC053-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W3390

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To							
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity			
W3399	286A3399				AUTOPILOT AB1050R ELEV AND STANDBY RUDDER PCU, SYSTEM - B (continued)													
1004	20	HE	D		14-0	22-12-41	D43399J	34			D01687	21			YC053-YN236, YN501-YR328			
1004Z			D		0-0	22-12-41	D43399J	S/R			GD00973	ST..	E	*4	YC053-YN236, YN501-YR328			
1005	20	HE	E		5-1	27-24-11	D43399J	35			D43389J	8			YC053-YN236, YN501-YR328			
1005Z			E		0-0	27-24-11	D43399J	S/R			D43389J	S/R			YC053-YN236, YN501-YR328			
1009	20	HE	I		5-1	27-24-11	D43399J	48			D43389J	9			YC053-YN236, YN501-YR328			
1009Z			I		0-0	27-24-11	D43399J	S/R			D43389J	S/R			YC053-YN236, YN501-YR328			
1010	20	HE	J		2-10	22-12-41	D01687	2			GD00973	DC..	E	*2	YC053-YN236, YN501-YR328			
1010Z			J		0-0	22-12-41	D01687			AB	GD00973	DC..	E	*2	YC053-YD153			
1010Z			J		0-0	22-12-41	D01687	DED			GD00973	DC..	E	*2	YD154-YN236, YN501-YR328			
1011	20	HE	K		2-10	22-12-41	D01687	22			GD00973	DC..	E	*3	YC053-YN236, YN501-YR328			
1011Z			K		0-0	22-12-41	D01687			AB	GD00973	DC..	E	*3	YC053-YD153			
1011Z			K		0-0	22-12-41	D01687	DED			GD00973	DC..	E	*3	YD154-YN236, YN501-YR328			
2001B	22	HF	AA		16-2	22-12-41	D01677	1			D43399J	4			YC053-YN236, YN501-YR328			
2001R	22	HF	AA		0-0	22-12-41	D01677	2			D43399J	3			YC053-YN236, YN501-YR328			
2001Z			AA		0-0	22-12-41	D01677	S/R			D43399J	S/R			YC053-YN236, YN501-YR328			
2003B	22	HF	AC		17-2	22-12-41	D02207	1			D43399J	8			YC053-YD157			
2003B	22	HF	AC		16-8	22-12-41	D02207	1			D43399J	8			YD158-YN236, YN501-YR328			
2003R	22	HF	AC		0-0	22-12-41	D02207	2			D43399J	7			YC053-YN236, YN501-YR328			
2003Z			AC		0-0	22-12-41	GD04811	ST..	E	*1	D43399J	S/R			YC053-YN236, YN501-YR328			
2004B	22	HF	AD		16-5	22-12-41	D01679	1			D43399J	6			YC053-YN236, YN501-YR328			
2004R	22	HF	AD		0-0	22-12-41	D01679	2			D43399J	5			YC053-YN236, YN501-YR328			

WIRE LIST

D280A108

91-21-11

Section W3390

Page 9

Nov 12/2012



WIRE LIST

91-21-11

Section W3390

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Fam	Description FT-IN Diagram		From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W3399	286A3399				AUTOPILOT AB1050R ELEV AND STANDBY RUDDER PCU, SYSTEM - B (continued)										
2011Z				AK	0-0	27-32-31	D43399J	S/R			D11409	S/R			YC053-YN236, YN501-YR328
3001B	22	HG	CA		14-0	22-12-41	D01687	12			D43399J	16			YC053-YN236, YN501-YR328
3001R	22	HG	CA		0-0	22-12-41	D01687	11			D43399J	15			YC053-YN236, YN501-YR328
3001Y	22	HG	CA		0-0	22-12-41	D01687	13			D43399J	17			YC053-YN236, YN501-YR328
3001Z			CA		0-0	22-12-41	D01687			AA	D43399J	S/R			YC053-YD153
3001Z			CA		0-0	22-12-41	GD00973	ST..	E	*1	D43399J	S/R			YD154-YN236, YN501-YR328
3002B	22	HG	CB		16-2	22-12-41	D43399J	19			D01677	4			YC053-YN236, YN501-YR314
3002B	22	HF	CB		16-2	22-12-41	D43399J	19			D01677	4			YR315-YR328
3002R	22	HG	CB		0-0	22-12-41	D43399J	18			D01677	5			YC053-YN236, YN501-YR314
3002R	22	HF	CB		0-0	22-12-41	D43399J	18			D01677	5			YR315-YR328
3002Y	22	HG	CB		0-0	22-12-41	D43399J	20			D01677	3			YC053-YN236, YN501-YR314
3002Z			CB		0-0	22-12-41	D43399J	S/R			D01677	S/R			YC053-YN236, YN501-YR328
3003B	22	HG	CC		16-5	22-12-41	D43399J	22			D01679	5			YC053-YN236, YN501-YR328
3003R	22	HG	CC		0-0	22-12-41	D43399J	21			D01679	4			YC053-YN236, YN501-YR328
3003Y	22	HG	CC		0-0	22-12-41	D43399J	23			D01679	3			YC053-YN236, YN501-YR328
3003Z			CC		0-0	22-12-41	D43399J	S/R			D01679	S/R			YC053-YN236, YN501-YR328
3005B	22	HG	CE		5-1	27-24-11	D43399J	29			D43389J	2			YC053-YN236, YN501-YR328
3005R	22	HG	CE		0-0	27-24-11	D43399J	28			D43389J	1			YC053-YN236, YN501-YR328
3005Y	22	HG	CE		0-0	27-24-11	D43399J	30			D43389J	3			YC053-YN236, YN501-YR328
3005Z			CE		0-0	27-24-11	D43399J	S/R			D43389J	S/R			YC053-YN236, YN501-YR328
3006B	22	HG	CF		12-5	SPARE	D43389J	11			D01687	REF	VP		YC053-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W3390

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3399	286A3399			AUTOPILOT AB1050R ELEV AND STANDBY RUDDER PCU, SYSTEM - B (continued)											
3006R	22	HG	CF		0-0	SPARE	D43389J	10			D01687	REF	VP		YC053-YN236, YN501-YR328
3006Y	22	HG	CF		0-0	SPARE	D43389J	12			D01687	REF	VP		YC053-YN236, YN501-YR328
3006Z			CF		0-0	SPARE	D43389J	S/R			D01687			AA	YC053-YD153
3006Z			CF		0-0	SPARE	D43389J	S/R			GD00973	ST..	E	*1	YD154-YN236, YN501-YR328
FRAA					0-0	22-12-41	D01687			AA	GD00973	ST..	E	*4	YC053-YD153

WIRE LIST

D280A108

91-21-11

Section W3390

Page 12 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3419	286A3419				EMERGENCY LOCATOR TRANSMITTER										
0001	22		PA		80-8	23-24-11	D04889J	1			D03003	1			YC051-YD170
0001	22		PA		80-5	23-24-11	D04889J	1			D03003	18			YL951-YL999, YR301-YR328
0001	22		PA		61-2	23-24-11	D04889J	1			D03003	18			YN231-YN501
0002	22		PA		80-8	23-24-11	D04889J	2			D03003	2			YC051-YD170
0002	22		PA		80-5	23-24-11	D04889J	2			D03003	8			YL951-YL999, YR301-YR328
0002	22		PA		61-2	23-24-11	D04889J	2			D03003	8			YN231-YN501
0003	22		PA		80-8	23-24-11	D04889J	3			D03003	3			YC051-YD170
0003	22		PA		80-5	23-24-11	D04889J	3			D03003	20			YL951-YL999, YR301-YR328
0003	22		PA		61-2	23-24-11	D04889J	3			D03003	20			YN231-YN501
0004	24		PK		2-0	23-24-11	D03003	10			D10717	2			YC051-YD170
0005	22		PA		0-7	23-24-11	D03003	5			D03003	8			YC051-YD170
0005	22		PA		0-7	23-24-11	D03003	14			D03003	16			YL951-YR328
0006	22		PA		80-8	23-24-11	D04889J	6			D03003	6			YC051-YD170
0006	22		PA		80-5	23-24-11	D04889J	6			D03003	22			YL951-YL999, YR301-YR328
0006	22		PA		61-2	23-24-11	D04889J	6			D03003	22			YN231-YN501
0007	22		PA		80-8	23-24-11	D04889J	7			D03003	7			YC051-YD170
0007	22		PA		80-5	23-24-11	D04889J	7			D03003	19			YL951-YL999, YR301-YR328
0007	22		PA		61-2	23-24-11	D04889J	7			D03003	19			YN231-YN501
0008	24		PK		2-0	23-24-11	D03003	9			D10717	10			YC051-YD170
0009	24		PK		2-0	23-24-11	D03003	12			D10717	9			YC051-YD170
0010	24		PK		80-5	23-24-11	D04889J	9			D10717	1			YC051-YD170
0011	22		PA		80-8	23-24-11	D04889J	11			D03003	11			YC051-YD170
0011	22		PA		80-5	23-24-11	D04889J	11			D03003	11			YL951-YL999, YR301-YR328
0011	22		PA		61-2	23-24-11	D04889J	11			D03003	11			YN231-YN501
0032	20		PA		5-0	23-24-11	D10717	11			GD03764	DC..	1		YC051-YD170
0033	20		PA		5-0	23-24-11	D10717	12			GD03764	DC..	1		YC051-YD170
0034	20		PA		6-9	23-24-11	M02115	26	1A		GD03764	DC..	1		YC051-YD170
0034	20		PA		6-7	23-24-11	M02115	26	1A		GD03764	DC..	1		YL951-YL999, YR301-YR328
0034	20		PA		6-8	23-24-11	M02115	26	1A		GD03764	DC..	1		YN231-YN501
0035	20		PA		4-11	23-24-11	D10715	25			GD03764	DC..	1		YC051-YD170
0035	20		PA		7-3	23-24-11	D11993	25			GD03764	DC..	1		YL951-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3410

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3419	286A3419				EMERGENCY LOCATOR TRANSMITTER (continued)										
0035	20		PA		7-4	23-24-11	D11993	25			GD03764	DC..	1		YN231-YN501
0036	20		PA		4-11	23-24-11	D10715	26			GD03764	DC..	1		YC051-YD170
0036	20		PA		7-3	23-24-11	D11993	26			GD03764	DC..	1		YL951-YL999, YR301-YR328
0036	20		PA		7-4	23-24-11	D11993	26			GD03764	DC..	1		YN231-YN501
0101	24		PK		2-10	23-24-11	D10715	1			M02115	1	1A		YC051-YD170
0101	24		PK		6-9	23-24-11	M02115	1	1A		D11993	1			YL951-YL999, YR301-YR328
0101	24		PK		6-9	23-24-11	D11993	1			M02115	1	1A		YN231-YN501
0102	24		PK		2-10	23-24-11	D10715	2			M02115	2	1A		YC051-YD170
0102	24		PK		6-9	23-24-11	M02115	2	1A		D11993	2			YL951-YL999, YR301-YR328
0102	24		PK		6-9	23-24-11	D11993	2			M02115	2	1A		YN231-YN501
0103	24		PK		2-10	23-24-11	D10715	3			M02115	3	1A		YC051-YD170
0103	24		PK		6-9	23-24-11	M02115	3	1A		D11993	3			YL951-YL999, YR301-YR328
0103	24		PK		6-9	23-24-11	D11993	3			M02115	3	1A		YN231-YN501
0104	24		PK		2-10	23-24-11	D10715	4			M02115	4	1A		YC051-YD170
0104	24		PK		6-9	23-24-11	M02115	4	1A		D11993	4			YL951-YL999, YR301-YR328
0104	24		PK		6-9	23-24-11	D11993	4			M02115	4	1A		YN231-YN501
0105	24		PK		2-10	23-24-11	D10715	5			M02115	5	1A		YC051-YD170
0105	24		PK		6-9	23-24-11	M02115	5	1A		D11993	5			YL951-YL999, YR301-YR328
0105	24		PK		6-9	23-24-11	D11993	5			M02115	5	1A		YN231-YN501
0106	24		PK		2-10	23-24-11	D10715	6			M02115	6	1A		YC051-YD170
0106	24		PK		6-9	23-24-11	M02115	6	1A		D11993	6			YL951-YL999, YR301-YR328
0106	24		PK		6-9	23-24-11	D11993	6			M02115	6	1A		YN231-YN501
0107	24		PK		2-10	23-24-11	D10715	7			M02115	7	1A		YC051-YD170
0107	24		PK		6-9	23-24-11	M02115	7	1A		D11993	7			YL951-YL999, YR301-YR328
0107	24		PK		6-9	23-24-11	D11993	7			M02115	7	1A		YN231-YN501
0108	24		PK		2-10	23-24-11	D10715	8			M02115	8	1A		YC051-YD170
0108	24		PK		6-9	23-24-11	M02115	8	1A		D11993	8			YL951-YL999, YR301-YR328
0108	24		PK		6-9	23-24-11	D11993	8			M02115	8	1A		YN231-YN501
0109	24		PK		2-10	23-24-11	D10715	9			M02115	9	1A		YC051-YD170

WIRE LIST

D280A108

91-21-11

Section W3410

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3419	286A3419				EMERGENCY LOCATOR TRANSMITTER (continued)											
0109	24		PK		6-9	23-24-11		M02115	9	1A		D11993	9			YL951-YL999, YR301-YR328
0109	24		PK		6-9	23-24-11		D11993	9			M02115	9	1A		YN231-YN501
0110	24		PK		2-10	23-24-11		D10715	10			M02115	10	1A		YC051-YD170
0110	24		PK		6-9	23-24-11		M02115	10	1A		D11993	10			YL951-YL999, YR301-YR328
0110	24		PK		6-9	23-24-11		D11993	10			M02115	10	1A		YN231-YN501
0111	24		PK		2-10	23-24-11		D10715	11			M02115	11	1A		YC051-YD170
0111	24		PK		6-9	23-24-11		M02115	11	1A		D11993	11			YL951-YL999, YR301-YR328
0111	24		PK		6-9	23-24-11		D11993	11			M02115	11	1A		YN231-YN501
0112	24		PK		2-10	23-24-11		D10715	12			M02115	12	1A		YC051-YD170
0112	24		PK		6-9	23-24-11		M02115	12	1A		D11993	12			YL951-YL999, YR301-YR328
0112	24		PK		6-9	23-24-11		D11993	12			M02115	12	1A		YN231-YN501
0113	24		PK		2-10	23-24-11		D10715	13			M02115	13	1A		YC051-YD170
0113	24		PK		6-9	23-24-11		M02115	13	1A		D11993	13			YL951-YL999, YR301-YR328
0113	24		PK		6-9	23-24-11		D11993	13			M02115	13	1A		YN231-YN501
0114	24		PK		2-10	23-24-11		D10715	14			M02115	14	1A		YC051-YD170
0114	24		PK		6-9	23-24-11		M02115	14	1A		D11993	14			YL951-YL999, YR301-YR328
0114	24		PK		6-9	23-24-11		D11993	14			M02115	14	1A		YN231-YN501
0115	24		PK		2-10	23-24-11		D10715	15			M02115	15	1A		YC051-YD170
0115	24		PK		6-9	23-24-11		M02115	15	1A		D11993	15			YL951-YL999, YR301-YR328
0115	24		PK		6-9	23-24-11		D11993	15			M02115	15	1A		YN231-YN501
0116	24		PK		2-10	23-24-11		D10715	16			M02115	16	1A		YC051-YD170
0116	24		PK		6-9	23-24-11		M02115	16	1A		D11993	16			YL951-YL999, YR301-YR328
0116	24		PK		6-9	23-24-11		D11993	16			M02115	16	1A		YN231-YN501
0117	24		PK		2-10	23-24-11		D10715	17			M02115	17	1A		YC051-YD170
0117	24		PK		6-9	23-24-11		M02115	17	1A		D11993	17			YL951-YL999, YR301-YR328
0117	24		PK		6-9	23-24-11		D11993	17			M02115	17	1A		YN231-YN501
0118	24		PK		2-10	23-24-11		D10715	18			M02115	18	1A		YC051-YD170
0118	24		PK		6-9	23-24-11		M02115	18	1A		D11993	18			YL951-YL999, YR301-YR328
0118	24		PK		6-9	23-24-11		D11993	18			M02115	18	1A		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3410

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W3419	286A3419				EMERGENCY LOCATOR TRANSMITTER (continued)												
0119	24		PK		2-10	23-24-11		D10715	19			M02115	19	1A		YC051-YD170	
0119	24		PK		6-9	23-24-11		M02115	19	1A		D11993	19			YL951-YL999, YR301-YR328	
0119	24		PK		6-9	23-24-11		D11993	19			M02115	19	1A		YN231-YN501	
0120	24		PK		2-10	23-24-11		D10715	20			M02115	20	1A		YC051-YD170	
0120	24		PK		6-9	23-24-11		M02115	20	1A		D11993	20			YL951-YL999, YR301-YR328	
0120	24		PK		6-9	23-24-11		D11993	20			M02115	20	1A		YN231-YN501	
0121	24		PK		2-10	23-24-11		D10715	21			M02115	21	1A		YC051-YD170	
0121	24		PK		6-9	23-24-11		M02115	21	1A		D11993	21			YL951-YL999, YR301-YR328	
0121	24		PK		6-9	23-24-11		D11993	21			M02115	21	1A		YN231-YN501	
0122	24		PK		2-10	23-24-11		D10715	22			M02115	22	1A		YC051-YD170	
0122	24		PK		6-9	23-24-11		M02115	22	1A		D11993	22			YL951-YL999, YR301-YR328	
0122	24		PK		6-9	23-24-11		D11993	22			M02115	22	1A		YN231-YN501	
0123	24		PK		2-10	23-24-11		D10715	23			M02115	23	1A		YC051-YD170	
0123	24		PK		6-9	23-24-11		M02115	23	1A		D11993	23			YL951-YL999, YR301-YR328	
0123	24		PK		6-9	23-24-11		D11993	23			M02115	23	1A		YN231-YN501	
0124	24		PK		2-10	23-24-11		D10715	24			M02115	24	1A		YC051-YD170	
0124	24		PK		6-9	23-24-11		M02115	24	1A		D11993	24			YL951-YL999, YR301-YR328	
0124	24		PK		6-9	23-24-11		D11993	24			M02115	24	1A		YN231-YN501	
2001B	24		Y2	AB	80-5	34-61-15		D04889J	5			D10717	4	VP		YC051-YD170	
2001R	24		Y2	AB	0-0	34-61-15		D04889J	4			D10717	3	VP		YC051-YD170	
2001Z				AB	0-0	34-61-15		D04889J	8			D10717	DED			YC051-YD170	

WIRE LIST

D280A108

91-21-11

Section W3410

Page 4 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

	Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I	W3477	286A3477			IFE -(BSI) DIGITAL VIDEO SYSTEM INTEGRATION											
I	0001	20		PA		6-1	44-21-10	SP00823			9	SM00002		9		YN501-YR328
I	0002	20		PA		6-1	44-21-10	SP00825			9	SM00003		9		YN501-YR328
I	0004	20		PA		2-1	44-21-12	GD08057	DC..	1		D12899J	2			YN501-YR328
I	0005	20		PA		2-1	44-21-12	GD08057	AC..	1		D12899J	3			YN501-YR328
I	0006	20		PA		2-1	44-21-12	GD08057	ST..	1		D12899J	4			YN501-YR328
I	0007	20		PA		2-11	44-21-12	SM00003			9	D12899J	10	VP		YN501-YR328
I	0008	20		CQ		2-11	44-21-12	SM00002			9	D12899J	5	VP		YN501-YR328
I	0009	20		PA		2-0	44-21-12	D12899J		7		D12887J	1			YN501-YR328
I	0010	20		CQ		2-11	44-21-12	SM00002			9	D12887J	2			YN501-YR328
I	0011	20		CQ		2-1	44-21-12	GD08057	DC..	1		D12887J	3			YN501-YR328
I	0012	20		PA		2-1	44-21-12	GD08057	ST..	1		D12887J	4			YN501-YR328
	0019	22		PA		19-7	44-21-12	SM00001			9	D12899J	1			YN501-YR319
I	0019	22		PA		19-8	44-21-12	SM00001			9	D12899J	1			YR320-YR328
	0027	22		PA		14-10	44-21-22	D45227P		1		D45912P	21			YN501-YR301
	0027	22		PA		15-8	44-21-22	D45227P		1		D45912P	21			YR303-YR319
I	0027	22		PA		15-10	44-21-22	D45227P		1		D45912P	21			YR320-YR328
	0028	22		PA		14-10	44-21-22	D45227P		15		D45912P	16			YN501-YR301
	0028	22		PA		15-8	44-21-22	D45227P		15		D45912P	16			YR303-YR319
I	0028	22		PA		15-10	44-21-22	D45227P		15		D45912P	16			YR320-YR328
	0029	22		PA		14-10	44-21-22	D45227P		3		D45912P	18			YN501-YR301
	0029	22		PA		15-8	44-21-22	D45227P		3		D45912P	18			YR303-YR319
I	0029	22		PA		15-10	44-21-22	D45227P		3		D45912P	18			YR320-YR328
	0030	22		PA		14-10	44-21-22	D45227P		16		D45912P	17			YN501-YR301
	0030	22		PA		15-8	44-21-22	D45227P		16		D45912P	17			YR303-YR319
I	0030	22		PA		15-10	44-21-22	D45227P		16		D45912P	17			YR320-YR328
	0031	22		PA		5-4	44-21-22	SM00001			9	D45912P	15			YN501-YR301
I	0031	22		PA		6-4	44-21-22	SM00001			9	D45912P	15			YR303-YR328
	0032	22		PA		14-10	44-21-22	D45227P		2		D45912P	19			YN501-YR301
	0032	22		PA		15-8	44-21-22	D45227P		2		D45912P	19			YR303-YR319
I	0032	22		PA		15-10	44-21-22	D45227P		2		D45912P	19			YR320-YR328
	0033	22		PA		14-10	44-21-22	D45227P		6		D45912P	20			YN501-YR301
	0033	22		PA		15-8	44-21-22	D45227P		6		D45912P	20			YR303-YR319
I	0033	22		PA		15-10	44-21-22	D45227P		6		D45912P	20			YR320-YR328
	0035	20		PA		21-11	44-21-10	SM00003			9	D45912P	5			YN501-YR301
	0035	20		PA		22-6	44-21-10	SM00003			9	D45912P	5			YR303-YR319
I	0035	20		PA		22-7	44-21-10	SM00003			9	D45912P	5			YR320-YR328
I	0036	20		PA		2-8	44-21-12	SM00003			9	D40011J	10	VP		YN501-YR328
	0037	20		CQ		2-8	44-21-12	SM00002			9	D40011J	5	VP		YN501-YR301
I	0037	20		CQ		2-8	44-21-12	SM00002			9	D40011J	5			YR303-YR328

WIRE LIST

D280A108

91-21-11

Section W3470

Page 1

Nov 12/2012

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3477	286A3477			IFE -(BSI) DIGITAL VIDEO SYSTEM INTEGRATION (continued)										
0038	20		PA		4-8	44-21-12	GD08057	DC..	1		D40011J	2		YN501-YR328
0039	20		PA		4-8	44-21-12	GD08057	AC..	1		D40011J	3		YN501-YR328
0040	20		PA		4-8	44-21-12	GD08057	ST..	1		D40011J	4		YN501-YR328
0041	22		PA		10-1	44-21-22	SM00001		9		D45227P	14		YN501-YR301
0041	22		PA		10-5	44-21-22	SM00001		9		D45227P	14		YR303-YR319
0041	22		PA		10-6	44-21-22	SM00001		9		D45227P	14		YR320-YR328
4001B	24		FS	KA	23-11	44-21-12	D45167P	A-4			D12883J	A-3		YN501-YR319
4001B	24		FS	KA	24-1	44-21-12	D45167P	A-4			D12883J	A-3		YR320-YR328
4001G	24		FS	KA	0-0	44-21-12	D45167P	A-3			D12883J	A-4		YN501-YR328
4001R	24		FS	KA	0-0	44-21-12	D45167P	A-2			D12883J	A-1		YN501-YR328
4001Y	24		FS	KA	0-0	44-21-12	D45167P	A-1			D12883J	A-2		YN501-YR328
4001Z				KA	0-0	44-21-12	D45167P	=CA			D12883J	=CA		YN501-YR328
4002B	24		FS	KB	23-11	44-21-12	D45167P	B-4			D12883J	B-3		YN501-YR319
4002B	24		FS	KB	24-1	44-21-12	D45167P	B-4			D12883J	B-3		YR320-YR328
4002G	24		FS	KB	0-0	44-21-12	D45167P	B-3			D12883J	B-4		YN501-YR328
4002R	24		FS	KB	0-0	44-21-12	D45167P	B-2			D12883J	B-1		YN501-YR328
4002Y	24		FS	KB	0-0	44-21-12	D45167P	B-1			D12883J	B-2		YN501-YR328
4002Z				KB	0-0	44-21-12	D45167P	=CB			D12883J	=CB		YN501-YR328
4003B	24		FS	KC	23-10	44-21-12	D45167P	C-4			D12885J	A-3		YN501-YR319
4003B	24		FS	KC	23-11	44-21-12	D45167P	C-4			D12885J	A-3		YR320-YR328
4003G	24		FS	KC	0-0	44-21-12	D45167P	C-3			D12885J	A-4		YN501-YR328
4003R	24		FS	KC	0-0	44-21-12	D45167P	C-2			D12885J	A-1		YN501-YR328
4003Y	24		FS	KC	0-0	44-21-12	D45167P	C-1			D12885J	A-2		YN501-YR328
4003Z				KC	0-0	44-21-12	D45167P	=CC			D12885J	=CA		YN501-YR328
4005B	24		FS	KE	4-10	44-21-12	D12897J	A-4			D12889J	A-3		YN501-YR328
4005G	24		FS	KE	0-0	44-21-12	D12897J	A-3			D12889J	A-4		YN501-YR328
4005R	24		FS	KE	0-0	44-21-12	D12897J	A-2			D12889J	A-1		YN501-YR328
4005Y	24		FS	KE	0-0	44-21-12	D12897J	A-1			D12889J	A-2		YN501-YR328
4005Z				KE	0-0	44-21-12	D12897J	=CA			D12889J	=CA		YN501-YR328
4006B	24		FS	KF	4-10	44-21-12	D12897J	B-4			D12889J	B-3		YN501-YR328
4006G	24		FS	KF	0-0	44-21-12	D12897J	B-3			D12889J	B-4		YN501-YR328
4006R	24		FS	KF	0-0	44-21-12	D12897J	B-2			D12889J	B-1		YN501-YR328
4006Y	24		FS	KF	0-0	44-21-12	D12897J	B-1			D12889J	B-2		YN501-YR328
4006Z				KF	0-0	44-21-12	D12897J	=CB			D12889J	=CB		YN501-YR328
4007B	24		FS	KG	4-7	44-21-12	D45449J	A-3			D12891J	A-3		YN501-YR328
4007G	24		FS	KG	0-0	44-21-12	D45449J	A-4			D12891J	A-4		YN501-YR328
4007R	24		FS	KG	0-0	44-21-12	D45449J	A-1			D12891J	A-1		YN501-YR328
4007Y	24		FS	KG	0-0	44-21-12	D45449J	A-2			D12891J	A-2		YN501-YR328
4007Z				KG	0-0	44-21-12	D45449J	=CA			D12891J	=CA		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W3470

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3477	286A3477				IFE -(BSI) DIGITAL VIDEO SYSTEM INTEGRATION (continued)											
4008B	24	FS		KH	4-7	44-21-12		D45449J		B-3		D12891J		B-3		YN501-YR328
4008G	24	FS		KH	0-0	44-21-12		D45449J		B-4		D12891J		B-4		YN501-YR328
4008R	24	FS		KH	0-0	44-21-12		D45449J		B-1		D12891J		B-1		YN501-YR328
4008Y	24	FS		KH	0-0	44-21-12		D45449J		B-2		D12891J		B-2		YN501-YR328
4008Z				KH	0-0	44-21-12		D45449J		=CB		D12891J		=CB		YN501-YR328
4009B	24	FS		KI	23-11	44-21-12		D45169P		A-3		D12893J		A-3		YN501-YR319
4009B	24	FS		KI	24-0	44-21-12		D45169P		A-3		D12893J		A-3		YR320-YR328
4009G	24	FS		KI	0-0	44-21-12		D45169P		A-4		D12893J		A-4		YN501-YR328
4009R	24	FS		KI	0-0	44-21-12		D45169P		A-1		D12893J		A-1		YN501-YR328
4009Y	24	FS		KI	0-0	44-21-12		D45169P		A-2		D12893J		A-2		YN501-YR328
4009Z				KI	0-0	44-21-12		D45169P		=CA		D12893J		=CA		YN501-YR328
4010B	24	FS		KJ	23-11	44-21-12		D45169P		B-3		D12893J		B-3		YN501-YR319
4010B	24	FS		KJ	24-0	44-21-12		D45169P		B-3		D12893J		B-3		YR320-YR328
4010G	24	FS		KJ	0-0	44-21-12		D45169P		B-4		D12893J		B-4		YN501-YR328
4010R	24	FS		KJ	0-0	44-21-12		D45169P		B-1		D12893J		B-1		YN501-YR328
4010Y	24	FS		KJ	0-0	44-21-12		D45169P		B-2		D12893J		B-2		YN501-YR328
4010Z				KJ	0-0	44-21-12		D45169P		=CB		D12893J		=CB		YN501-YR328
4011B	24	FS		KK	23-10	44-21-12		D45169P		C-3		D12895J		A-3		YN501-YR319
4011B	24	FS		KK	23-11	44-21-12		D45169P		C-3		D12895J		A-3		YR320-YR328
4011G	24	FS		KK	0-0	44-21-12		D45169P		C-4		D12895J		A-4		YN501-YR328
4011R	24	FS		KK	0-0	44-21-12		D45169P		C-1		D12895J		A-1		YN501-YR328
4011Y	24	FS		KK	0-0	44-21-12		D45169P		C-2		D12895J		A-2		YN501-YR328
4011Z				KK	0-0	44-21-12		D45169P		=CC		D12895J		=CA		YN501-YR328
4012B	24	FS		KL	23-10	44-21-12		D45169P		D-3		D12895J		B-3		YN501-YR319
4012B	24	FS		KL	23-11	44-21-12		D45169P		D-3		D12895J		B-3		YR320-YR328
4012G	24	FS		KL	0-0	44-21-12		D45169P		D-4		D12895J		B-4		YN501-YR328
4012R	24	FS		KL	0-0	44-21-12		D45169P		D-1		D12895J		B-1		YN501-YR328
4012Y	24	FS		KL	0-0	44-21-12		D45169P		D-2		D12895J		B-2		YN501-YR328
4012Z				KL	0-0	44-21-12		D45169P		=CD		D12895J		=CB		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W3470

Page 3 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3497		286A3497					IFE - (BSI) SERVER BASED SYSTEM PSU OVERHEAD VIDEO									
0001		20		PA		4-9	44-21-36	GD08054	ST..	1		D45421J			AA	YN501-YR328
0002		20		PA		4-9	44-21-36	GD08054	ST..	1		D45421J	3			YN501-YR328
0004		20		PA		10-3	44-21-37	D45425J		3		GD03754	ST..	1		YN501
0004		20		PA		9-2	44-21-37	D45425J		3		GD03754	ST..	1		YR301-YR328
0005		20		PA		10-3	44-21-37	D45425J			AB	GD03754	ST..	1		YN501
0005		20		PA		9-2	44-21-37	D45425J			AB	GD03754	ST..	1		YR301-YR328
0006		20		PA		6-1	44-21-46	GD03854	ST..	1		D45429J			AC	YN501-YR314
0006		20		PA		6-11	44-21-46	GD03854	ST..	1		D45429J			AC	YR315-YR328
0007		20		PA		6-1	44-21-46	GD03854	ST..	1		D45429J	3			YN501-YR314
0007		20		PA		6-11	44-21-46	GD03854	ST..	1		D45429J	3			YR315-YR328
0008		20		PA		4-5	44-21-47	GD03996	ST..	1		D45433J			AD	YN501
0008		20		PA		6-7	44-21-47	GD03996	ST..	1		D45433J			AD	YR301-YR328
0009		20		PA		4-5	44-21-47	GD03996	ST..	1		D45433J	3			YN501
0009		20		PA		6-7	44-21-47	GD03996	ST..	1		D45433J	3			YR301-YR328
0011		18		PA		4-9	44-21-36	GD08054	ST..	1		D45421J	7	18		YN501-YR328
0012		18		PA		6-1	44-21-46	GD03854	ST..	1		D45429J	7	18		YN501-YR314
0012		18		PA		6-11	44-21-46	GD03854	ST..	1		D45429J	7	18		YR315-YR328
001CO					JA	0-0	44-21-36	D45195P	=CV			D45427J	=CB			YN501-YR328
001CX				OF	JA	21-6	44-21-36	D45195P	V-1	PQ		D45427J	B-1	PP		YN501-YR328
002CO					JB	0-0	44-21-36	D45439P	=C1			D45427J	=CC			YN501-YR328
002CX				OF	JB	20-8	44-21-36	D45439P	=A1			D45427J	C-1	PP		YN501-YR328
004CO					JD	0-0	44-21-46	D45199P	=CV			D45435J	=CB			YN501-YR328
004CX				OF	JD	33-0	44-21-46	D45199P	V-1	PQ		D45435J	B-1	PP		YN501-YR314
004CX				OF	JD	33-2	44-21-46	D45199P	V-1	PQ		D45435J	B-1	PP		YR315-YR328
005CO					JE	0-0	44-21-46	D45441P	=C1			D45435J	=CC			YN501-YR328
005CX				OF	JE	32-4	44-21-46	D45441P	=A1			D45435J	C-1	PP		YN501-YR314
005CX				OF	JE	32-6	44-21-46	D45441P	=A1			D45435J	C-1	PP		YR315-YR328
2501B		20		X2	AA	15-7	44-21-36	D45233P		4		D45421J	5			YN501-YR328
2501R		20		X2	AA	0-0	44-21-36	D45233P		3		D45421J	4			YN501-YR328
2501Z					AA	0-0	44-21-36	D45233P	DED			D45421J			AA	YN501-YR328
2502B		24		OT	AB	21-10	44-21-36	D45195P	J			D45421J	9			YN501-YR328
2502W		24		OT	AB	0-0	44-21-36	D45195P	H			D45421J	8			YN501-YR328
2502Z					AB	0-0	44-21-36	D45195P	K			D45421J	10			YN501-YR328
2503B		20		X2	AC	43-1	44-21-37	D45233P		8		D45425J	5			YN501
2503B		20		X2	AC	53-5	44-21-37	D45233P		8		D45425J	5			YR301-YR328
2503R		20		X2	AC	0-0	44-21-37	D45233P		7		D45425J	4			YN501-YR328
2503Z					AC	0-0	44-21-37	D45233P	DED			D45425J			AB	YN501-YR328
2505B		20		X2	AE	20-2	44-21-46	D45233P		6		D45429J	5			YN501-YR314
2505B		20		X2	AE	20-6	44-21-46	D45233P		6		D45429J	5			YR315-YR328

WIRE LIST

D280A108

91-21-11

Section W3490

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3497	286A3497				IFE - (BSI) SERVER BASED SYSTEM PSU OVERHEAD VIDEO (continued)										
2505R	20	X2		AE	0-0	44-21-46	D45233P	5			D45429J	4			YN501-YR328
2505Z				AE	0-0	44-21-46	D45233P	DED			D45429J			AC	YN501-YR328
2506B	24	OT		AF	33-5	44-21-46	D45199P	J			D45429J	9			YN501-YR314
2506B	24	OT		AF	33-9	44-21-46	D45199P	J			D45429J	9			YR315-YR328
2506W	24	OT		AF	0-0	44-21-46	D45199P	H			D45429J	8			YN501-YR328
2506Z				AF	0-0	44-21-46	D45199P	K			D45429J	10			YN501-YR328
2507B	20	X2		AG	46-11	44-21-47	D45233P	10			D45433J	5			YN501
2507B	20	X2		AG	57-1	44-21-47	D45233P	10			D45433J	5			YR301-YR328
2507R	20	X2		AG	0-0	44-21-47	D45233P	9			D45433J	4			YN501-YR328
2507Z				AG	0-0	44-21-47	D45233P	DED			D45433J			AD	YN501-YR328
4001B	24	FS		KA	22-0	44-21-36	D45195P	U-4			D45427J	A-4			YN501-YR328
4001G	24	FS		KA	0-0	44-21-36	D45195P	U-3			D45427J	A-3			YN501-YR328
4001R	24	FS		KA	0-0	44-21-36	D45195P	U-2			D45427J	A-2			YN501-YR328
4001Y	24	FS		KA	0-0	44-21-36	D45195P	U-1			D45427J	A-1			YN501-YR328
4001Z				KA	0-0	44-21-36	D45195P	=CU			D45427J	=CA			YN501-YR328
4003B	24	FS		KC	33-6	44-21-46	D45199P	U-4			D45435J	A-4			YN501-YR314
4003B	24	FS		KC	33-8	44-21-46	D45199P	U-4			D45435J	A-4			YR315-YR328
4003G	24	FS		KC	0-0	44-21-46	D45199P	U-3			D45435J	A-3			YN501-YR328
4003R	24	FS		KC	0-0	44-21-46	D45199P	U-2			D45435J	A-2			YN501-YR328
4003Y	24	FS		KC	0-0	44-21-46	D45199P	U-1			D45435J	A-1			YN501-YR328
4003Z				KC	0-0	44-21-46	D45199P	=CU			D45435J	=CA			YN501-YR328
FRAA					0-0	44-21-36	D45421J	6			D45421J			AA	YN501-YR328
FRAB					0-0	44-21-37	D45425J			AB	D45425J	6			YN501-YR328
FRAC					0-0	44-21-46	D45429J	6			D45429J			AC	YN501-YR328
FRAD					0-0	44-21-47	D45433J			AD	D45433J	6			YN501-YR328

WIRE LIST

D280A108

91-21-11
Section W3490
Page 2 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From						To					
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I	W3509	286A3509			HF-1 E8-1 TO STA 1030											
	0005	20		PA		112-9	23-11-11	D04227J		5		D08509P	A01			YC051-YC052
	0005	20		PA		113-4	23-11-11	D04227J		5		D08509P	A01			YC053-YC055
I	0005	20		PA		113-9	23-11-11	D04227J		5		D08509P	A01			YC056-YD170
	0007	22		PA		112-9	23-11-11	D04227J		7		D08509P	B01			YC051-YC052
	0007	22		PA		113-4	23-11-11	D04227J		7		D08509P	B01			YC053-YC055
I	0007	22		PA		113-9	23-11-11	D04227J		7		D08509P	B01			YC056-YD170
	0008	22		PA		112-9	23-11-11	D04227J		8		D08509P	A02			YC051-YC052
	0008	22		PA		113-4	23-11-11	D04227J		8		D08509P	A02			YC053-YC055
I	0008	22		PA		113-9	23-11-11	D04227J		8		D08509P	A02			YC056-YD170
	0009	20		PA		112-9	23-11-11	D04227J		9		D08509P	B02			YC051-YC052
	0009	20		PA		113-4	23-11-11	D04227J		9		D08509P	B02			YC053-YC055
I	0009	20		PA		113-9	23-11-11	D04227J		9		D08509P	B02			YC056-YD170
	0010	20		PA		112-9	23-11-11	D04227J		10		D08509P	A03			YC051-YC052
	0010	20		PA		113-4	23-11-11	D04227J		10		D08509P	A03			YC053-YC055
I	0010	20		PA		113-9	23-11-11	D04227J		10		D08509P	A03			YC056-YD170
	0011	22		PA		112-9	23-11-11	D04227J		11		D08509P	B03			YC051-YC052
	0011	22		PA		113-4	23-11-11	D04227J		11		D08509P	B03			YC053-YC055
I	0011	22		PA		113-9	23-11-11	D04227J		11		D08509P	B03			YC056-YD170
	0012	20		PA		112-9	23-11-11	D08509P		B04		D04227J	12			YC051-YC052
	0012	20		PA		113-4	23-11-11	D08509P		B04		D04227J	12			YC053-YC055
I	0012	20		PA		113-9	23-11-11	D08509P		B04		D04227J	12			YC056-YD157
	0012	20		PA		113-9	23-11-11	D08509P		A04		D04227J	12			YD158-YD170
	0013	20		PA		112-9	23-11-11	D08509P		B05		D04227J	13			YC051-YC052
	0013	20		PA		113-4	23-11-11	D08509P		B05		D04227J	13			YC053-YC055
I	0013	20		PA		113-9	23-11-11	D08509P		B05		D04227J	13			YC056-YD157
	0013	20		PA		113-9	23-11-11	D08509P		B04		D04227J	13			YD158-YD170
	0014	18		PA		112-9	23-11-11	D04227J		14		D08509P	G			YC051-YC052
	0014	18		PA		113-4	23-11-11	D04227J		14		D08509P	G			YC053-YC055
I	0014	18		PA		113-9	23-11-11	D04227J		14		D08509P	G			YC056-YD170
	0016	18		PA		112-9	23-11-11	D04227J		16		D08509P	F			YC051-YC052
	0016	18		PA		113-4	23-11-11	D04227J		16		D08509P	F			YC053-YC055
I	0016	18		PA		113-9	23-11-11	D04227J		16		D08509P	F			YC056-YD170

WIRE LIST

D280A108

91-21-11

Section W3500

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3511		286A3511			HF-2 E8-1 TO STA 1030											
0005		20		PA		114-0	23-11-21	D04245J		5		D08811P	A01			YD158-YD170
0007		22		PA		114-0	23-11-21	D04245J		7		D08811P	B01			YD158-YD170
0008		22		PA		114-0	23-11-21	D04245J		8		D08811P	A02			YD158-YD170
0009		20		PA		114-0	23-11-21	D04245J		9		D08811P	B02			YD158-YD170
0010		20		PA		114-0	23-11-21	D04245J		10		D08811P	A03			YD158-YD170
0011		22		PA		114-0	23-11-21	D04245J		11		D08811P	B03			YD158-YD170
0012		20		PA		114-0	23-11-21	D04245J		12		D08811P	B04			YD158-YD170
0013		20		PA		114-0	23-11-21	D04245J		13		D08811P	B05			YD158-YD170
0014		18		PA		114-0	23-11-21	D04245J		14		D08811P	G			YD158-YD170
0016		18		PA		114-0	23-11-21	D04245J		16		D08811P	F			YD158-YD170
W3517		286A3517			HF-1 E8-1 TO STA 1030 ANT FEED											
001CO					AA	0-0	23-11-11	D04217J	=	C1		D08517P	=	C1		YC051-YD170
001CX				0G	AA	110-10	23-11-11	D04217J	=	A1		D08517P	=	A1		YC051-YC055
001CX				0G	AA	111-11	23-11-11	D04217J	=	A1		D08517P	=	A1		YC056-YD170

WIRE LIST

D280A108

91-21-11
Section W3510
Page 1 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3523	286A3523				HF-2 E8-1 COAX TO STA 1030 ANT FEED										
001CO				AA	0-0	23-11-21	D04713J	= C1			D08823P	= C1			YD158-YD170
001CX		0G		AA	112-3	23-11-21	D04713J	= A1			D08823P	= A1			YD158-YD170

For training purposes only!

WIRE LIST

D280A108

91-21-11

Section W3520

Page 1 End

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I	W3553	286A3553	HF-1 E6-2 TO STA 1030												
I	0005	20	PA		30-7	23-11-11	D04227J		5		D40121P	A01			YL951-YR328
I	0007	22	PA		30-7	23-11-11	D04227J		7		D40121P	B01			YL951-YR328
I	0008	22	PA		30-7	23-11-11	D04227J		8		D40121P	A02			YL951-YR328
I	0009	20	PA		30-7	SPARE	D04227J		9		D40121P	B02			YL951-YR328
I	0010	20	PA		30-7	SPARE	D04227J		10		D40121P	A03			YL951-YR328
I	0011	22	PA		30-7	23-11-11	D04227J		11		D40121P	B03			YL951-YR328
I	0012	20	PA		30-7	23-11-11	D40121P		A04		D04227J	12			YL951-YR328
I	0013	20	PA		30-7	23-11-11	D40121P		B04		D04227J	13			YL951-YR328
I	0014	18	PA		30-7	23-11-11	D04227J		14		D40121P	G			YL951-YR328
I	0016	18	PA		30-7	23-11-11	D04227J		16		D40121P	F			YL951-YR328
I	W3555	286A3555	HF-2 E6-2 TO STA 1030												
I	0005	20	PA		30-10	23-11-21	D04245J		5		D40125P	A01			YL951-YR328
I	0007	22	PA		30-10	23-11-21	D04245J		7		D40125P	B01			YL951-YR328
I	0008	22	PA		30-10	23-11-21	D04245J		8		D40125P	A02			YL951-YR328
I	0009	20	PA		30-10	SPARE	D04245J		9		D40125P	B02			YL951-YR328
I	0010	20	PA		30-10	SPARE	D04245J		10		D40125P	A03			YL951-YR328
I	0011	22	PA		30-10	23-11-21	D04245J		11		D40125P	B03			YL951-YR328
I	0012	20	PA		30-10	23-11-21	D04245J		12		D40125P	B04			YL951-YR328
I	0013	20	PA		30-10	23-11-21	D04245J		13		D40125P	B05			YL951-YR328
I	0014	18	PA		30-10	23-11-21	D04245J		14		D40125P	G			YL951-YR328
I	0016	18	PA		30-10	23-11-21	D04245J		16		D40125P	F			YL951-YR328
I	W3557	286A3557	HF-1 E6-2 TO STA 1030 ANT FEED												
I	001CO		AA		0-0	23-11-11	D04217J		=C1		D40123P	=C1			YL951-YR328
I	001CX		0G AA		29-5	23-11-11	D04217J		=A1		D40123P	=A1			YL951-YR328
I	W3559	286A3559	HF-2 E6-2 COAX TO STA 1030 ANT FEED												
I	001CO		AA		0-0	23-11-21	D04713J		=C1		D40127P	=C1			YL951-YR328
I	001CX		0G AA		29-4	23-11-21	D04713J		=A1		D40127P	=A1			YL951-YR328

WIRE LIST

D280A108

91-21-11
Section W3550
Page 1 End
Nov 12/2012

Bundle No.	Part Number			Description	From			To							
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice
W3577	286A3577			EE BAY TO AFT RH STOW BIN											
0001	20		PA		32-9	23-32-21	D43277P	A10			D45287J	1			YC051-YC055
0001	20		PA		32-10	23-32-21	D43277P	A10			D45287J	1			YC056-YD157
0001	20		PA		32-10	23-32-21	D45287J	1			D43277P	A10			YD158-YD170
0001	20		PA		30-4	23-32-21	D45287J	16			D40151P	A09			YL951-YL967
0001	20		PA		90-0	23-32-21	D45297J	16			D40151P	A09			YN231-YN235
001CO				AA	0-0	23-32-21	D45287J	= C15			D43279P	= C1			YD158-YD170
001CO				IA	0-0	23-32-21	D40151P	B06			D45287J	= 15			YL951-YL999
001CO				IA	0-0	23-32-21	D40151P	B06			D45297J	= 15			YN231-YN260
001CX			0F	AA	33-9	23-32-21	D45287J	15			D43279P	= A1			YD158-YD170
001CX			0F	IA	29-10	23-32-21	D40151P	A06			D45287J	15			YL951-YL999
001CX			0F	IA	89-0	23-32-21	D40151P	A06			D45297J	15			YN231-YN260
2501B	24		0T	AA	32-9	23-32-21	D43277P	B03			D45287J	3			YC051-YC055
2501B	24		0T	AA	32-10	23-32-21	D43277P	B03			D45287J	3			YC056-YD157
2501B	24		0T	AB	32-10	23-32-21	D45287J	3			D43277P	B03			YD158-YD170
2501B	24		0T	AA	30-4	23-32-21	D40151P	B01			D45287J	3			YL951-YL999
2501B	24		0T	AA	90-0	23-32-21	D40151P	B01			D45297J	3			YN231-YN260
2501W	24		0T	AA	0-0	23-32-21	D43277P	A03			D45287J	2			YC051-YD157
2501W	24		0T	AB	0-0	23-32-21	D45287J	2			D43277P	A03			YD158-YD170
2501W	24		0T	AA	0-0	23-32-21	D40151P	A01			D45287J	2			YL951-YL999
2501W	24		0T	AA	0-0	23-32-21	D40151P	A01			D45297J	2			YN231-YN260
2501Z				AA	0-0	23-32-21	D43277P	PERG	1F		D45287J	4			YC051-YD157
2501Z				AB	0-0	23-32-21	D45287J	4			D43277P	PERG	1F		YD158-YD170
2501Z				AA	0-0	23-32-21	D40151P	PERG	1F		D45287J	4			YL951-YL999
2501Z				AA	0-0	23-32-21	D40151P	PERG	1F		D45297J	4			YN231-YN260
2502B	24		7P	AB	32-9	23-32-21	D43277P	A04			D45287J	5			YC051-YC055
2502B	24		7P	AB	32-10	23-32-21	D43277P	A04			D45287J	5			YC056-YD157
2502B	22		X2	AC	32-10	SPARE	D45287J	6			D43277P	B04			YD158-YD170
2502B	24		7P	AB	30-4	23-32-21	D40151P	A02			D45287J	5			YL951-YL999
2502B	24		7P	AB	90-0	23-32-21	D40151P	A02			D45297J	5			YN231-YN260
2502BN	24		7P	AB	0-0	23-32-21	D43277P	B04			D45287J	6			YC051-YD157
2502BN	24		7P	AB	0-0	23-32-21	D40151P	B02			D45287J	6			YL951-YL999
2502BN	24		7P	AB	0-0	23-32-21	D40151P	B02			D45297J	6			YN231-YN260
2502R	22		X2	AC	0-0	SPARE	D45287J	5			D43277P	A04			YD158-YD170
2502Z				AB	0-0	23-32-21	D43277P	PERG	1F		D45287J	7			YC051-YD157
2502Z				AC	0-0	SPARE	D45287J	DED			D43277P	PERG	1F		YD158-YD170
2502Z				AB	0-0	23-32-21	D40151P	PERG	1F		D45287J	7			YL951-YL999
2502Z				AB	0-0	23-32-21	D40151P	PERG	1F		D45297J	7			YN231-YN260
2503B	24		Y2	AC	32-9	23-32-21	D43277P	B05			D45287J	9			YC051-YC055
2503B	24		Y2	AC	32-10	23-32-21	D43277P	B05			D45287J	9			YC056-YD157

WIRE LIST

D280A108

91-21-11

Section W3570

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3577	286A3577			EE BAY TO AFT RH STOW BIN (continued)											
2503B	24	Y2	AC		30-4	23-32-21	D40151P	B10			D45287J	9			YL951-YL999
2503B	24	Y2	AC		90-0	23-32-21	D40151P	B10			D45297J	9			YN231-YN260
2503R	24	Y2	AC		0-0	23-32-21	D43277P	A05			D45287J	8			YC051-YD157
2503R	24	Y2	AC		0-0	23-32-21	D40151P	A10			D45287J	8			YL951-YL999
2503R	24	Y2	AC		0-0	23-32-21	D40151P	A10			D45297J	8			YN231-YN260
2503Z			AC		0-0	23-32-21	D43277P	A06			D45287J	10			YC051-YD157
2503Z			AC		0-0	23-32-21	D40151P	PERG	1F		D45287J	10			YL951-YL999
2503Z			AC		0-0	23-32-21	D40151P	PERG	1F		D45297J	10			YN231-YN260
2504B	24	Y2	AD		30-4	23-32-21	D40151P	B04			D45287J	22			YL951-YL999
2504B	24	Y2	AD		90-0	23-32-21	D40151P	B04			D45297J	22			YN231-YN260
2504R	24	Y2	AD		0-0	23-32-21	D40151P	A04			D45287J	21			YL951-YL999
2504R	24	Y2	AD		0-0	23-32-21	D40151P	A04			D45297J	21			YN231-YN260
2504Z			AD		0-0	23-32-21	D40151P	PERG	1F		D45287J			AA	YL951-YL999
2504Z			AD		0-0	23-32-21	D40151P	PERG	1F		D45297J	23			YN231-YN260
2505B	24	Y2	AE		32-10	23-32-21	D45287J	9			D43277P	B05			YD158-YD170
2505B	24	Y2	AE		30-4	23-32-21	D40151P	B03			D45287J	20			YL951-YL999
2505B	24	Y2	AE		90-0	23-32-21	D40151P	B03			D45297J	20			YN231-YN260
2505R	24	Y2	AE		0-0	23-32-21	D45287J	8			D43277P	A05			YD158-YD170
2505R	24	Y2	AE		0-0	23-32-21	D40151P	A03			D45287J	19			YL951-YL999
2505R	24	Y2	AE		0-0	23-32-21	D40151P	A03			D45297J	19			YN231-YN260
2505Z			AE		0-0	23-32-21	D45287J	DED			D43277P	A06			YD158-YD170
2505Z			AE		0-0	23-32-21	D40151P	PERG	1F		D45287J			AA	YL951-YL999
2505Z			AE		0-0	23-32-21	D40151P	PERG	1F		D45297J	24			YN231-YN260
2506B	24	Y2	AF		30-4	23-32-21	D40151P	B05			D45287J	18			YL951-YL999
2506B	24	Y2	AF		90-0	23-32-21	D40151P	B05			D45297J	18			YN231-YN260
2506R	24	Y2	AF		0-0	23-32-21	D40151P	A05			D45287J	17			YL951-YL999
2506R	24	Y2	AF		0-0	23-32-21	D40151P	A05			D45297J	17			YN231-YN260
2506Z			AF		0-0	23-32-21	D40151P	PERG	1F		D45287J	25			YL951-YL999
2506Z			AF		0-0	23-32-21	D40151P	PERG	1F		D45297J	25			YN231-YN260
FRAA					0-0	23-32-21	D45287J			AA	D45287J	23			YL951-YL999

WIRE LIST

D280A108

91-21-11
Section W3570
Page 2 End
Nov 12/2012



WIRE LIST

91-21-11

Section W3580

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3583	286A3583				VIDEO - VCC TO DISC BRACKET (NEAR CLUSTER 3) AND TO AB0340B (continued)											
0016	22		PA		10-0	23-32-12		D45283J	34			D45231J	34			YC051-YD157
0016	20		PA		2-0	23-32-13		GD08057	ST..	1		D45281J	31			YD158-YD170
0016	20		PA		2-1	23-32-13		D45281J	31			GD08057	ST..	1		YL951-YL999
0016	20		PA		3-6	23-32-11		D45289J	31			GD04270	ST..	1		YN231-YN260
0017	22		PA		10-0	23-32-12		D45283J	35			D45231J	35			YC051-YD157
0017	22		PA		10-0	23-32-14		D45283J	35			D45231J	35			YD158-YD170
0017	22		PA		10-3	23-32-14		D45283J	35			D45231J	35			YL951-YL999
0017	22		PA		70-6	23-32-14		D45285J	35			D45231J	35			YN231-YN260
0019	22		PA		9-0	23-34-01		D12213J	39			D45231J	43			YL951-YN235
0019	22		PA		9-1	23-34-01		D12213J	39			D45231J	43			YN236-YN260
0030	22		PA		10-0	23-32-14		D45283J	47			D45231J	45			YD158-YD170
0030	22		PA		10-3	23-32-14		D45283J	47			D45231J	45			YL951-YL999
0030	22		PA		70-6	23-32-14		D45285J	47			D45231J	45			YN231-YN260
0031	20		PA		46-3	23-32-11		D45275P	CAP	Y		D45289J	3			YL951-YL999
0032	20		PA		3-3	23-32-11		GD04270	DC..	1		D45289J	4			YL951-YL999
0033	20		PA		3-3	23-32-11		GD04270	ST..	1		D45289J	5			YL951-YL999
0034	20		PA		3-3	23-32-11		GD04270	ST..	1		D45289J	31			YL951-YL999
0035	22		PA		89-8	23-32-12		D45231J	CAP	Y		D45285J	28			YL951-YL999
0036	22		PA		89-8	23-32-12		D45231J	CAP	Y		D45285J	30			YL951-YL999
0037	22		PA		10-0	SPARE		D45231J	37			D45283J	37			YD158-YD170
0037	22		PA		89-8	23-32-12		D45231J	CAP	Y		D45285J	22			YL951-YL999
0038	22		PA		89-8	23-32-12		D45231J	CAP	Y		D45285J	27			YL951-YL999
0039	22		PA		89-8	23-32-14		D45231J	CAP	Y		D45285J	20			YL951-YL999
0040	22		PA		89-8	23-32-14		D45231J	CAP	Y		D45285J	47			YL951-YL999
0041	22		PA		89-8	23-32-14		D45231J	CAP	Y		D45285J	46			YL951-YL999
0042	22		PA		89-8	23-32-14		D45231J	CAP	Y		D45285J	38			YL951-YL999
0043	22		PA		89-8	23-32-14		D45231J	CAP	Y		D45285J	34			YL951-YL999
0044	22		PA		89-8	23-32-14		D45231J	CAP	Y		D45285J	35			YL951-YL999
0045	22		PA		89-8	23-32-14		D45231J	CAP	Y		D45285J	21			YL951-YL999
0086	22		PA		10-0	23-32-14		D45283J	46			D45231J	46			YD158-YD170
0086	22		PA		10-3	23-32-14		D45283J	46			D45231J	46			YL951-YL999
0086	22		PA		70-6	23-32-14		D45285J	46			D45231J	46			YN231-YN260
0087	22		PA		10-0	23-32-14		D45231J	34			D45283J	34			YD158-YD170
0087	22		PA		10-3	23-32-14		D45283J	34			D45231J	34			YL951-YL999
0087	22		PA		70-6	23-32-14		D45285J	34			D45231J	34			YN231-YN260
2001B	20		PB	EA	8-11	23-32-11		D45253J	3			D45281J	2			YC059-YD170
2001B	20		PB	EA	59-5	23-32-11		D45275P	3			D45281J	2			YL951-YL999
2001B	20		PB	EA	37-0	23-32-11		D45275P	3			D45289J	2			YN231-YN260
2001R	20		PB	EA	0-0	23-32-11		D45253J	1			D45281J	1			YC059-YD170

WIRE LIST

D280A108

91-21-11

Section W3580

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Diagram	From				To				Effectivity	
	Wire No.	GA	CO TY			Fam	FT-IN	Equip	Term	Type	Splice	Equip	Term		Type
W3583	286A3583			VIDEO - VCC TO DISC BRACKET (NEAR CLUSTER 3) AND TO AB0340B (continued)											
2001R	20	PB	EA	0-0	23-32-11	D45275P	2			D45281J	1			YL951-YL999	
2001R	20	PB	EA	0-0	23-32-11	D45275P	2			D45289J	1			YN231-YN260	
2002B	20	PB	EB	46-3	23-32-11	D45275P	CAP	Y		D45289J	2			YL951-YL999	
2002R	20	PB	EB	0-0	23-32-11	D45275P	CAP	Y		D45289J	1			YL951-YL999	
2501B	22	X2	AA	10-0	23-32-12	D45283J	6			D45231J	6			YC051-YD170	
2501B	22	X2	AA	10-11	23-32-12	D45283J	6			D12213J	6			YL951-YL999	
2501B	22	X2	AA	63-10	23-32-12	D45285J	6			D12213J	6			YN231-YN235	
2501B	22	X2	AA	63-11	23-32-12	D45285J	6			D12213J	6			YN236-YN260	
2501R	22	X2	AA	0-0	23-32-12	D45283J	5			D45231J	5			YC051-YD170	
2501R	22	X2	AA	0-0	23-32-12	D45283J	5			D12213J	5			YL951-YL999	
2501R	22	X2	AA	0-0	23-32-12	D45285J	5			D12213J	5			YN231-YN260	
2501Z			AA	0-0	23-32-12	D45283J			AA	D45231J			AB	YC051-YD170	
2501Z			AA	0-0	23-32-12	D45283J			AA	D12213J		PERB		YL951-YL999	
2501Z			AA	0-0	23-32-12	D45285J			AA	D12213J		PERB		YN231-YN260	
2502B	22	X2	AB	10-0	23-32-12	D45283J	8			D45231J	8			YC051-YD170	
2502B	22	X2	AB	10-11	23-32-12	D45283J	8			D12213J	8			YL951-YL999	
2502B	22	X2	AB	63-10	23-32-12	D45285J	8			D12213J	8			YN231-YN235	
2502B	22	X2	AB	63-11	23-32-12	D45285J	8			D12213J	8			YN236-YN260	
2502R	22	X2	AB	0-0	23-32-12	D45283J	7			D45231J	7			YC051-YD170	
2502R	22	X2	AB	0-0	23-32-12	D45283J	7			D12213J	7			YL951-YL999	
2502R	22	X2	AB	0-0	23-32-12	D45285J	7			D12213J	7			YN231-YN260	
2502Z			AB	0-0	23-32-12	D45283J			AA	D45231J			AB	YC051-YD170	
2502Z			AB	0-0	23-32-12	D45283J			AA	D12213J		PERB		YL951-YL999	
2502Z			AB	0-0	23-32-12	D45285J			AA	D12213J		PERB		YN231-YN260	
2503B	22	X2	AC	10-0	23-32-12	D45283J	11			D45231J	11			YC051-YD170	
2503B	22	X2	AC	10-11	23-32-12	D45283J	10			D12213J	10			YL951-YL999	
2503B	22	X2	AC	63-10	23-32-12	D45285J	10			D12213J	10			YN231-YN235	
2503B	22	X2	AC	63-11	23-32-12	D45285J	10			D12213J	10			YN236-YN260	
2503R	22	X2	AC	0-0	23-32-12	D45283J	10			D45231J	10			YC051-YD170	
2503R	22	X2	AC	0-0	23-32-12	D45283J	9			D12213J	9			YL951-YL999	
2503R	22	X2	AC	0-0	23-32-12	D45285J	9			D12213J	9			YN231-YN260	
2503Z			AC	0-0	23-32-12	D45283J			AC	D45231J			AD	YC051-YD170	
2503Z			AC	0-0	23-32-12	D45283J			AA	D12213J		PERB		YL951-YL999	
2503Z			AC	0-0	23-32-12	D45285J			AA	D12213J		PERB		YN231-YN260	
2504B	22	X2	AD	10-0	23-32-12	D45283J	13			D45231J	13			YC051-YD170	
2504B	22	X2	AD	10-11	23-32-12	D45283J	13			D12213J	13			YL951-YL999	
2504B	22	X2	AD	63-10	23-32-12	D45285J	13			D12213J	13			YN231-YN235	
2504B	22	X2	AD	63-11	23-32-12	D45285J	13			D12213J	13			YN236-YN260	
2504R	22	X2	AD	0-0	23-32-12	D45283J	12			D45231J	12			YC051-YD170	

WIRE LIST

D280A108

91-21-11

Section W3580

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3583	286A3583			VIDEO - VCC TO DISC BRACKET (NEAR CLUSTER 3) AND TO AB0340B (continued)											
2504R	22	X2		AD	0-0	23-32-12	D45283J	12			D12213J	12			YL951-YL999
2504R	22	X2		AD	0-0	23-32-12	D45285J	12			D12213J	12			YN231-YN260
2504Z				AD	0-0	23-32-12	D45283J			AC	D45231J			AD	YC051-YD170
2504Z				AD	0-0	23-32-12	D45283J			AC	D12213J		PERB		YL951-YL999
2504Z				AD	0-0	23-32-12	D45285J			AC	D12213J		PERB		YN231-YN260
2505B	22	X2		AE	10-0	23-32-12	D45283J	16			D45231J	16			YC051-YD170
2505B	22	X2		AE	10-11	23-32-12	D45283J	15			D12213J	15			YL951-YL999
2505B	22	X2		AE	63-10	23-32-12	D45285J	15			D12213J	15			YN231-YN235
2505B	22	X2		AE	63-11	23-32-12	D45285J	15			D12213J	15			YN236-YN260
2505R	22	X2		AE	0-0	23-32-12	D45283J	15			D45231J	15			YC051-YD170
2505R	22	X2		AE	0-0	23-32-12	D45283J	14			D12213J	14			YL951-YL999
2505R	22	X2		AE	0-0	23-32-12	D45285J	14			D12213J	14			YN231-YN260
2505Z				AE	0-0	23-32-12	D45283J			AE	D45231J			AF	YC051-YD170
2505Z				AE	0-0	23-32-12	D45283J			AC	D12213J		PERB		YL951-YL999
2505Z				AE	0-0	23-32-12	D45285J			AC	D12213J		PERB		YN231-YN260
2506B	22	X2		AF	10-0	23-32-12	D45283J	18			D45231J	18			YC051-YD170
2506B	22	X2		AF	10-11	23-32-12	D45283J	17			D12213J	17			YL951-YL999
2506B	22	X2		AF	63-10	23-32-12	D45285J	17			D12213J	17			YN231-YN235
2506B	22	X2		AF	63-11	23-32-12	D45285J	17			D12213J	17			YN236-YN260
2506R	22	X2		AF	0-0	23-32-12	D45283J	17			D45231J	17			YC051-YD170
2506R	22	X2		AF	0-0	23-32-12	D45283J	16			D12213J	16			YL951-YL999
2506R	22	X2		AF	0-0	23-32-12	D45285J	16			D12213J	16			YN231-YN260
2506Z				AF	0-0	23-32-12	D45283J			AE	D45231J			AF	YC051-YD170
2506Z				AF	0-0	23-32-12	D45283J			AC	D12213J		PERB		YL951-YL999
2506Z				AF	0-0	23-32-12	D45285J			AC	D12213J		PERB		YN231-YN260
2507B	22	X2		AG	10-0	23-32-12	D45283J	3			D45231J	3			YC051-YD170
2507B	22	X2		AG	10-3	23-32-12	D45283J	3			D45231J	3			YL951-YL999
2507B	22	X2		AG	70-6	23-32-12	D45285J	3			D45231J	3			YN231-YN260
2507R	22	X2		AG	0-0	23-32-12	D45283J	2			D45231J	2			YC051-YL999
2507R	22	X2		AG	0-0	23-32-12	D45285J	2			D45231J	2			YN231-YN260
2507Z				AG	0-0	23-32-12	D45283J			AG	D45231J			AH	YC051-YD157
2507Z				AG	0-0	23-32-12	D45283J	4			D45231J	4			YD158-YL999
2507Z				AG	0-0	23-32-12	D45285J	4			D45231J	4			YN231-YN260
2508B	22	X2		AH	10-0	23-32-12	D45283J	25			D45231J	25			YC051-YD170
2508B	22	X2		AH	10-3	23-32-12	D45283J	25			D45231J	25			YL951-YL999
2508B	22	X2		AH	70-6	23-32-12	D45285J	25			D45231J	25			YN231-YN260
2508R	22	X2		AH	0-0	23-32-12	D45283J	24			D45231J	24			YC051-YL999
2508R	22	X2		AH	0-0	23-32-12	D45285J	24			D45231J	24			YN231-YN260
2508Z				AH	0-0	23-32-12	D45283J			AG	D45231J			AH	YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W3580

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To							
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice
W3583	286A3583			VIDEO - VCC TO DISC BRACKET (NEAR CLUSTER 3) AND TO AB0340B (continued)											
2508Z				AH	0-0	23-32-12	D45283J	DED			D45231J	DED			YD158-YD170
2508Z				AH	0-0	23-32-12	D45283J	26			D45231J	26			YL951-YL999
2508Z				AH	0-0	23-32-12	D45285J	26			D45231J	26			YN231-YN260
2509B	24	OT		AI	10-0	23-32-12	D45283J	27			D45231J	27			YC051-YD157
2509B	22	X2		AI	10-0	23-32-12	D45283J	27			D45231J	27			YD158-YD170
2509R	22	X2		AI	0-0	23-32-12	D45283J	26			D45231J	26			YD158-YD170
2509W	24	OT		AI	0-0	23-32-12	D45283J	26			D45231J	26			YC051-YD157
2509Z				AI	0-0	23-32-12	D45283J	4			D45231J	4			YC051-YD157
2509Z				AI	0-0	23-32-12	D45283J	DED			D45231J	DED			YD158-YD170
2510B	24	OT		AJ	59-6	23-32-31	D45281J	7			D45275P	7			YC051-YD170
2510B	24	OT		AJ	59-5	23-32-31	D45275P	7			D45281J	7			YL951-YL999
2510B	24	OT		AJ	37-0	23-32-31	D45275P	7			D45289J	7			YN231-YN260
2510W	24	OT		AJ	0-0	23-32-31	D45281J	6			D45275P	6			YC051-YD170
2510W	24	OT		AJ	0-0	23-32-31	D45275P	6			D45281J	6			YL951-YL999
2510W	24	OT		AJ	0-0	23-32-31	D45275P	6			D45289J	6			YN231-YN260
2510Z				AJ	0-0	23-32-31	D45281J	8			D45275P	8			YC051-YD170
2510Z				AJ	0-0	23-32-31	D45275P	8			D45281J	8			YL951-YL999
2510Z				AJ	0-0	23-32-31	D45275P	8			D45289J	8			YN231-YN260
2511B	24	7P		AK	59-6	23-32-31	D45281J	9			D45275P	9			YC051-YD170
2511B	24	7P		AK	59-5	23-32-31	D45281J	9			D45275P	9			YL951-YL999
2511B	24	7P		AK	37-0	23-32-31	D45289J	9			D45275P	9			YN231-YN260
2511BN	24	7P		AK	0-0	23-32-31	D45281J	10			D45275P	10			YC051-YL999
2511BN	24	7P		AK	0-0	23-32-31	D45289J	10			D45275P	10			YN231-YN260
2511Z				AK	0-0	23-32-31	D45281J	11			D45275P	11			YC051-YL999
2511Z				AK	0-0	23-32-31	D45289J	11			D45275P	11			YN231-YN260
2512B	24	7P		AL	59-6	23-32-31	D45281J	12			D45275P	12			YC051-YD170
2512B	24	7P		AL	59-5	23-32-31	D45281J	12			D45275P	12			YL951-YL999
2512B	24	7P		AL	37-0	23-32-31	D45289J	12			D45275P	12			YN231-YN260
2512BN	24	7P		AL	0-0	23-32-31	D45281J	13			D45275P	13			YC051-YL999
2512BN	24	7P		AL	0-0	23-32-31	D45289J	13			D45275P	13			YN231-YN260
2512Z				AL	0-0	23-32-31	D45281J	14			D45275P	14			YC051-YL999
2512Z				AL	0-0	23-32-31	D45289J	14			D45275P	14			YN231-YN260
2513B	24	7P		AM	59-6	23-32-31	D45281J	15			D45275P	15			YC051-YD170
2513B	24	7P		AM	59-5	23-32-31	D45281J	15			D45275P	15			YL951-YL999
2513B	24	7P		AM	37-0	23-32-31	D45289J	15			D45275P	15			YN231-YN260
2513BN	24	7P		AM	0-0	23-32-31	D45281J	16			D45275P	16			YC051-YL999
2513BN	24	7P		AM	0-0	23-32-31	D45289J	16			D45275P	16			YN231-YN260
2513Z				AM	0-0	23-32-31	D45281J	17			D45275P	17			YC051-YL999
2513Z				AM	0-0	23-32-31	D45289J	17			D45275P	17			YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W3580

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity			
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice	
W3583	286A3583			VIDEO - VCC TO DISC BRACKET (NEAR CLUSTER 3) AND TO AB0340B (continued)												
2514B	24		0T	AN	59-6	23-32-51	D45281J		19		D45275P		19		YC051-YD170	
2514B	24		0T	AN	59-5	23-32-51	D45281J		19		D45275P		19		YL951-YL999	
2514B	24		0T	AN	37-0	23-32-51	D45289J		19		D45275P		19		YN231-YN260	
2514W	24		0T	AN	0-0	23-32-51	D45281J		18		D45275P		18		YC051-YL999	
2514W	24		0T	AN	0-0	23-32-51	D45289J		18		D45275P		18		YN231-YN260	
2514Z				AN	0-0	23-32-51	D45281J		20		D45275P		20		YC051-YL999	
2514Z				AN	0-0	23-32-51	D45289J		20		D45275P		20		YN231-YN260	
2515B	24		7P	AP	59-6	23-32-51	D45281J		21		D45275P		21		YC051-YD170	
2515B	24		7P	AP	59-5	23-32-51	D45281J		21		D45275P		21		YL951-YL999	
2515B	24		7P	AP	37-0	23-32-51	D45289J		21		D45275P		21		YN231-YN260	
2515BN	24		7P	AP	0-0	23-32-51	D45281J		22		D45275P		22		YC051-YL999	
2515BN	24		7P	AP	0-0	23-32-51	D45289J		22		D45275P		22		YN231-YN260	
2515Z				AP	0-0	23-32-51	D45281J		23		D45275P		23		YC051-YL999	
2515Z				AP	0-0	23-32-51	D45289J		23		D45275P		23		YN231-YN260	
2516B	24		7P	AQ	59-6	23-32-51	D45281J		24		D45275P		24		YC051-YD170	
2516B	24		7P	AQ	59-5	23-32-51	D45281J		24		D45275P		24		YL951-YL999	
2516B	24		7P	AQ	37-0	23-32-51	D45289J		24		D45275P		24		YN231-YN260	
2516BN	24		7P	AQ	0-0	23-32-51	D45281J		25		D45275P		25		YC051-YL999	
2516BN	24		7P	AQ	0-0	23-32-51	D45289J		25		D45275P		25		YN231-YN260	
2516Z				AQ	0-0	23-32-51	D45281J		26		D45275P		26		YC051-YL999	
2516Z				AQ	0-0	23-32-51	D45289J		26		D45275P		26		YN231-YN260	
2517B	24		7P	AR	59-6	23-32-51	D45281J		27		D45275P		27		YC051-YD170	
2517B	24		7P	AR	59-5	23-32-51	D45281J		27		D45275P		27		YL951-YL999	
2517B	24		7P	AR	37-0	23-32-51	D45289J		27		D45275P		27		YN231-YN260	
2517BN	24		7P	AR	0-0	23-32-51	D45281J		28		D45275P		28		YC051-YL999	
2517BN	24		7P	AR	0-0	23-32-51	D45289J		28		D45275P		28		YN231-YN260	
2517Z				AR	0-0	23-32-51	D45281J		29		D45275P		29		YC051-YL999	
2517Z				AR	0-0	23-32-51	D45289J		29		D45275P		29		YN231-YN260	
2518B	24		0T	AS	10-0	23-32-12	D45283J		32		D45231J		32		YC051-YD157	
2518B	24		0T	AS	10-0	SPARE	D45283J		41		D45231J		41		YD158-YD170	
2518B	24		0T	AS	10-11	23-32-12	D45283J		54		D12213J		54		YL951-YL999	
2518B	24		0T	AS	63-10	23-32-12	D45285J		54		D12213J		54		YN231-YN235	
2518B	24		0T	AS	63-11	23-32-12	D45285J		54		D12213J		54		YN236-YN260	
2518W	24		0T	AS	0-0	23-32-12	D45283J		31		D45231J		31		YC051-YD157	
2518W	24		0T	AS	0-0	SPARE	D45283J		42		D45231J		42		YD158-YD170	
2518W	24		0T	AS	0-0	23-32-12	D45283J		53		D12213J		53		YL951-YL999	
2518W	24		0T	AS	0-0	23-32-12	D45285J		53		D12213J		53		YN231-YN260	
2518Z				AS	0-0	23-32-12	D45283J		33		D45231J		33		YC051-YD157	
2518Z				AS	0-0	SPARE	D45283J		DED		D45231J		DED		YD158-YD170	

WIRE LIST

D280A108

91-21-11

Section W3580

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From			To			Effectivity			
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice	
W3583	286A3583			VIDEO - VCC TO DISC BRACKET (NEAR CLUSTER 3) AND TO AB0340B (continued)												
2518Z				AS	0-0	23-32-12	D45283J	55			D12213J	PERB		YL951-YL999		
2518Z				AS	0-0	23-32-12	D45285J	55			D12213J	PERB		YN231-YN260		
2519B	22		X2	AT	9-0	23-34-01	D12213J	41			D45231J	49		YL951-YN235		
2519B	22		X2	AT	9-1	23-34-01	D12213J	41			D45231J	49		YN236-YN260		
2519R	22		X2	AT	0-0	23-34-01	D12213J	40			D45231J	48		YL951-YN260		
2519Z				AT	0-0	23-34-01	D12213J	PERB			D45231J	50		YL951-YN260		
2520B	22		X2	AU	83-0	23-32-12	D12213J	CAP	Y		D45285J	6		YL951-YL999		
2520R	22		X2	AU	0-0	23-32-12	D12213J	CAP	Y		D45285J	5		YL951-YL999		
2520Z				AU	0-0	23-32-12	D12213J	DED			D45285J		AD	YL951-YL999		
2521B	22		X2	AV	83-0	23-32-12	D12213J	CAP	Y		D45285J	8		YL951-YL999		
2521R	22		X2	AV	0-0	23-32-12	D12213J	CAP	Y		D45285J	7		YL951-YL999		
2521Z				AV	0-0	23-32-12	D12213J	DED			D45285J		AD	YL951-YL999		
2522B	22		X2	AW	83-0	23-32-12	D12213J	CAP	Y		D45285J	10		YL951-YL999		
2522R	22		X2	AW	0-0	23-32-12	D12213J	CAP	Y		D45285J	9		YL951-YL999		
2522Z				AW	0-0	23-32-12	D12213J	DED			D45285J		AD	YL951-YL999		
2523B	22		X2	AX	83-0	23-32-12	D12213J	CAP	Y		D45285J	13		YL951-YL999		
2523R	22		X2	AX	0-0	23-32-12	D12213J	CAP	Y		D45285J	12		YL951-YL999		
2523Z				AX	0-0	23-32-12	D12213J	DED			D45285J		AE	YL951-YL999		
2524B	22		X2	AY	83-0	23-32-12	D12213J	CAP	Y		D45285J	15		YL951-YL999		
2524R	22		X2	AY	0-0	23-32-12	D12213J	CAP	Y		D45285J	14		YL951-YL999		
2524Z				AY	0-0	23-32-12	D12213J	DED			D45285J		AE	YL951-YL999		
2525B	22		X2	AZ	83-0	23-32-12	D12213J	CAP	Y		D45285J	17		YL951-YL999		
2525R	22		X2	AZ	0-0	23-32-12	D12213J	CAP	Y		D45285J	16		YL951-YL999		
2525Z				AZ	0-0	23-32-12	D12213J	DED			D45285J		AE	YL951-YL999		
2526B	24		0T	BA	83-0	23-32-12	D12213J	CAP	Y		D45285J	54		YL951-YL999		
2526W	24		0T	BA	0-0	23-32-12	D12213J	CAP	Y		D45285J	53		YL951-YL999		
2526Z				BA	0-0	23-32-12	D12213J	DED			D45285J	55		YL951-YL999		
2527B	22		X2	BB	89-8	23-32-12	D45231J	CAP	Y		D45285J	25		YL951-YL999		
2527R	22		X2	BB	0-0	23-32-12	D45231J	CAP	Y		D45285J	24		YL951-YL999		
2527Z				BB	0-0	23-32-12	D45231J	DED			D45285J	26		YL951-YL999		
2528B	22		X2	BC	89-8	23-32-12	D45231J	CAP	Y		D45285J	3		YL951-YL999		
2528R	22		X2	BC	0-0	23-32-12	D45231J	CAP	Y		D45285J	2		YL951-YL999		
2528Z				BC	0-0	23-32-12	D45231J	DED			D45285J	4		YL951-YL999		
2529B	24		0T	BD	46-3	23-32-31	D45289J	7			D45275P	CAP	Y	YL951-YL999		
2529W	24		0T	BD	0-0	23-32-31	D45289J	6			D45275P	CAP	Y	YL951-YL999		
2529Z				BD	0-0	23-32-31	D45289J	8			D45275P	DED		YL951-YL999		
2530B	24		7P	BE	46-3	23-32-31	D45289J	9			D45275P	CAP	Y	YL951-YL999		
2530BN	24		7P	BE	0-0	23-32-31	D45289J	10			D45275P	CAP	Y	YL951-YL999		
2530Z				BE	0-0	23-32-31	D45289J	11			D45275P	DED		YL951-YL999		

WIRE LIST

D280A108

91-21-11

Section W3580

Page 7

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3583	286A3583				VIDEO - VCC TO DISC BRACKET (NEAR CLUSTER 3) AND TO AB0340B (continued)										
2531B	24	7P	BF		46-3	23-32-31	D45289J		12		D45275P	CAP	Y		YL951-YL999
2531BN	24	7P	BF		0-0	23-32-31	D45289J		13		D45275P	CAP	Y		YL951-YL999
2531Z			BF		0-0	23-32-31	D45289J		14		D45275P	DED			YL951-YL999
2532B	24	7P	BG		46-3	23-32-31	D45289J		15		D45275P	CAP	Y		YL951-YL999
2532BN	24	7P	BG		0-0	23-32-31	D45289J		16		D45275P	CAP	Y		YL951-YL999
2532Z			BG		0-0	23-32-31	D45289J		17		D45275P	DED			YL951-YL999
2533B	24	0T	BH		46-3	23-32-51	D45289J		19		D45275P	CAP	Y		YL951-YL999
2533W	24	0T	BH		0-0	23-32-51	D45289J		18		D45275P	CAP	Y		YL951-YL999
2533Z			BH		0-0	23-32-51	D45289J		20		D45275P	DED			YL951-YL999
2534B	24	7P	BI		46-3	23-32-51	D45289J		21		D45275P	CAP	Y		YL951-YL999
2534BN	24	7P	BI		0-0	23-32-51	D45289J		22		D45275P	CAP	Y		YL951-YL999
2534Z			BI		0-0	23-32-51	D45289J		23		D45275P	DED			YL951-YL999
2535B	24	7P	BJ		46-3	23-32-51	D45289J		24		D45275P	CAP	Y		YL951-YL999
2535BN	24	7P	BJ		0-0	23-32-51	D45289J		25		D45275P	CAP	Y		YL951-YL999
2535Z			BJ		0-0	23-32-51	D45289J		26		D45275P	DED			YL951-YL999
2536B	24	7P	BK		46-3	23-32-51	D45289J		27		D45275P	CAP	Y		YL951-YL999
2536BN	24	7P	BK		0-0	23-32-51	D45289J		28		D45275P	CAP	Y		YL951-YL999
2536Z			BK		0-0	23-32-51	D45289J		29		D45275P	DED			YL951-YL999
3001B	22	PC	CA		10-0	23-32-12	D45231J		32		D45283J		32		YD158-YD170
3001B	22	PC	GA		10-11	23-32-12	D45283J		32		D12213J		32		YL951-YL999
3001B	22	PC	GA		63-10	23-32-12	D45285J		32		D12213J		32		YN231-YN235
3001B	22	PC	GA		63-11	23-32-12	D45285J		32		D12213J		32		YN236-YN260
3001R	22	PC	CA		0-0	23-32-12	D45231J		31		D45283J		31		YD158-YD170
3001R	22	PC	GA		0-0	23-32-12	D45283J		31		D12213J		31		YL951-YL999
3001R	22	PC	GA		0-0	23-32-12	D45285J		31		D12213J		31		YN231-YN260
3001Y	22	PC	CA		0-0	23-32-12	D45231J		33		D45283J		33		YD158-YD170
3001Y	22	PC	GA		0-0	23-32-12	D45283J		33		D12213J		33		YL951-YL999
3001Y	22	PC	GA		0-0	23-32-12	D45285J		33		D12213J		33		YN231-YN260
3002B	22	PC	GB		83-0	23-32-12	D12213J			CAP	Y	D45285J		32	YL951-YL999
3002R	22	PC	GB		0-0	23-32-12	D12213J			CAP	Y	D45285J		31	YL951-YL999
3002Y	22	PC	GB		0-0	23-32-12	D12213J			CAP	Y	D45285J		33	YL951-YL999
FRAA					0-0	23-32-12	D45283J				AA	D45283J		9	YC051-YD170
FRAA					0-0	23-32-12	D45283J				AA	D45283J		11	YL951-YL999
FRAA					0-0	23-32-12	D45285J				AA	D45285J		11	YN231-YN260
FRAB					0-0	23-32-12	D45231J				AB	D45231J		9	YC051-YD170
FRAC					0-0	23-32-12	D45283J				AC	D45283J		14	YC051-YD170
FRAC					0-0	23-32-12	D45283J				AC	D45283J		18	YL951-YL999
FRAC					0-0	23-32-12	D45285J				AC	D45285J		18	YN231-YN260
FRAD					0-0	23-32-12	D45231J				AD	D45231J		14	YC051-YD170

WIRE LIST

D280A108

91-21-11

Section W3580

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Diagram	From				To				Effectivity		
	Wire No.	GA	CO TY			Fam	FT-IN	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W3583	286A3583			VIDEO - VCC TO DISC BRACKET (NEAR CLUSTER 3) AND TO AB0340B (continued)												
FRA D					0-0	23-32-12	D45285J				AD	D45285J	11			YL951-YL999
FRA E					0-0	23-32-12	D45283J				AE	D45283J	19			YC051-YD170
FRA E					0-0	23-32-12	D45285J				AE	D45285J	18			YL951-YL999
FRA F					0-0	23-32-12	D45231J				AF	D45231J	19			YC051-YD170
FRA G					0-0	23-32-12	D45283J				AG	D45283J	39			YC051-YD157
FRA H					0-0	23-32-12	D45231J				AH	D45231J	39			YC051-YD157
W3589	286A3589			VIDEO - AC & DC POWER - P6 TO VCC AND TO VDU CLUSTERS 1 THRU 4												
0001	20		PA		15-6	23-32-11	D45233P		1			D45253P	1			YC051-YC052
0001	20		PA		15-10	23-32-11	D45233P		1			D45253P	1			YC053-YC058
0002	20		PA		15-6	23-32-11	D45233P		2			D45253P	2			YC051-YC052
0002	20		PA		15-10	23-32-11	D45233P		2			D45253P	2			YC053-YD170
0003	20		PA		2-5	23-32-31	D45259P				AA	GD03860	ST..	1		YC051-YD170
0004	20		PA		3-4	23-32-41	D45269P				AB	GD08012	ST..	1		YC051-YD170
0005	20		PA		2-5	23-32-51	D45271P				AC	GD04004	ST..	1		YC051-YD170
0006	20		PA		1-10	23-32-61	D45273P				AD	GD08028	ST..	1		YC051-YD170
2001B	20		PB	EA	15-10	23-32-11	D45233P		15			D45253P	3			YC059-YD170
2001R	20		PB	EA	0-0	23-32-11	D45233P		14			D45253P	1			YC059-YD170
2501B	18		X2	AA	24-8	23-32-31	D45233P		4	18		D45259P	2			YC051-YC052
2501B	18		X2	AA	25-0	23-32-31	D45233P		4	18		D45259P	2			YC053-YD170
2501R	18		X2	AA	0-0	23-32-31	D45233P		3	18		D45259P	1			YC051-YD170
2501Z				AA	0-0	23-32-31	D45233P		DED			D45259P			AA	YC051-YD170
2502B	18		X2	AB	42-7	23-32-41	D45233P		6	18		D45269P	2			YC051-YC052
2502B	18		X2	AB	42-11	23-32-41	D45233P		6	18		D45269P	2			YC053-YD170
2502R	18		X2	AB	0-0	23-32-41	D45233P		5	18		D45269P	1			YC051-YD170
2502Z				AB	0-0	23-32-41	D45233P		DED			D45269P			AB	YC051-YD170
2503B	18		X2	AC	64-1	23-32-51	D45233P		8	18		D45271P	2			YC051-YC052
2503B	18		X2	AC	64-5	23-32-51	D45233P		8	18		D45271P	2			YC053-YD170
2503R	18		X2	AC	0-0	23-32-51	D45233P		7	18		D45271P	1			YC051-YD170
2503Z				AC	0-0	23-32-51	D45233P		DED			D45271P			AC	YC051-YD170
2504B	18		X2	AD	86-1	23-32-61	D45233P		10	18		D45273P	2			YC051-YC052
2504B	18		X2	AD	86-5	23-32-61	D45233P		10	18		D45273P	2			YC053-YD170
2504R	18		X2	AD	0-0	23-32-61	D45233P		9	18		D45273P	1			YC051-YD170
2504Z				AD	0-0	23-32-61	D45233P		DED			D45273P			AD	YC051-YD170

WIRE LIST

D280A108

91-21-11

Section W3580

Page 9 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity			
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice	
W3591	286A3591				VIDEO - DISC BRKT (NEAR CLUSTER 3) - TO VDU CLUSTERS 1 & 3											
0001	20		PA		4-0	23-32-31	D10201		11			D45259J	1			YC051-YD170
0002	20		PA		4-0	23-32-31	D10201		12			D45259J	2			YC051-YD170
0003	20		PA		2-9	23-32-31	D10201		13			GD03860	ST..	1		YC051-YD153
0003	20		PA		2-10	23-32-31	D10201		13			GD03860	ST..	1		YD154-YD170
0004	20		PA		4-0	23-32-51	D10265		11			D45271J	1			YC051-YD170
0005	20		PA		4-0	23-32-51	D10265		12			D45271J	2			YC051-YD170
0006	20		PA		3-7	23-32-51	D10265		13			GD04004	ST..	1		YC051-YD153
0006	20		PA		3-8	23-32-51	D10265		13			GD04004	ST..	1		YD154-YD170
0007	20		PA		2-10	MULTI	D10201		19			GD03860	ST..	1		YD158-YD170
0008	20		PA		3-8	MULTI	D10265		19			GD04004	ST..	1		YD158-YD170
2501B	24		OT	AA	40-5	23-32-31	D10201		8			D45275J	7			YC051-YD153
2501B	24		OT	AA	40-6	23-32-31	D10201		8			D45275J	7			YD154-YD170
2501W	24		OT	AA	0-0	23-32-31	D10201		7			D45275J	6			YC051-YD170
2501Z				AA	0-0	23-32-31	D10201		9			D45275J	8			YC051-YD170
2502B	24		7P	AB	40-5	23-32-31	D10201		1			D45275J	9			YC051-YD153
2502B	24		7P	AB	40-6	23-32-31	D10201		1			D45275J	9			YD154-YD170
2502BN	24		7P	AB	0-0	23-32-31	D10201		2			D45275J	10			YC051-YD170
2502Z				AB	0-0	23-32-31	D10201		3			D45275J	11			YC051-YD170
2503B	24		7P	AC	40-5	23-32-31	D10201		4			D45275J	12			YC051-YD153
2503B	24		7P	AC	40-6	23-32-31	D10201		4			D45275J	12			YD154-YD170
2503BN	24		7P	AC	0-0	23-32-31	D10201		5			D45275J	13			YC051-YD170
2503Z				AC	0-0	23-32-31	D10201		6			D45275J	14			YC051-YD170
2504B	24		7P	AD	40-5	23-32-31	D10201		14			D45275J	15			YC051-YD153
2504B	24		7P	AD	40-6	23-32-31	D10201		14			D45275J	15			YD154-YD170
2504BN	24		7P	AD	0-0	23-32-31	D10201		15			D45275J	16			YC051-YD170
2504Z				AD	0-0	23-32-31	D10201		16			D45275J	17			YC051-YD170
2505B	24		OT	AE	2-11	23-32-51	D10265		8			D45275J	19			YC051-YD153
2505B	24		OT	AE	3-0	23-32-51	D10265		8			D45275J	19			YD154-YD170
2505W	24		OT	AE	0-0	23-32-51	D10265		7			D45275J	18			YC051-YD170
2505Z				AE	0-0	23-32-51	D10265		9			D45275J	20			YC051-YD170
2506B	24		7P	AF	2-11	23-32-51	D10265		1			D45275J	21			YC051-YD153
2506B	24		7P	AF	3-0	23-32-51	D10265		1			D45275J	21			YD154-YD170
2506BN	24		7P	AF	0-0	23-32-51	D10265		2			D45275J	22			YC051-YD170
2506Z				AF	0-0	23-32-51	D10265		3			D45275J	23			YC051-YD170
2507B	24		7P	AG	2-11	23-32-51	D10265		4			D45275J	24			YC051-YD153
2507B	24		7P	AG	3-0	23-32-51	D10265		4			D45275J	24			YD154-YD170
2507BN	24		7P	AG	0-0	23-32-51	D10265		5			D45275J	25			YC051-YD170
2507Z				AG	0-0	23-32-51	D10265		6			D45275J	26			YC051-YD170
2508B	24		7P	AH	2-11	23-32-51	D10265		14			D45275J	27			YC051-YD153

WIRE LIST

D280A108

91-21-11

Section W3590

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From			To					Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W3591	286A3591			VIDEO - DISC BRKT (NEAR CLUSTER 3) - TO VDU CLUSTERS 1 & 3 (continued)										
2508B	24	7P	AH	3-0	23-32-51	D10265	14			D45275J	27			YD154-YD170
2508BN	24	7P	AH	0-0	23-32-51	D10265	15			D45275J	28			YC051-YD170
2508Z			AH	0-0	23-32-51	D10265	16			D45275J	29			YC051-YD170
W3599	286A3599			VIDEO - VIDEO CONTROL CENTER - GALLEY G7										
0001	20	PA		4-9	23-32-11	D45281P	1			SM00001		S		YC051-YC052
0001	20	PA		4-9	23-32-11	D45281P	1			SM00020		S		YC053-YC058
0002	20	PA		4-9	23-32-11	D45281P	2			SM00002		S		YC051-YC058
0002	20	PA		2-7	44-21-12	D40011P	5			SM00013		9		YR303-YR328
0003	20	PA		4-9	23-32-11	D45281P	3			SM00003		S		YC051-YD157
0003	20	PA		4-2	23-32-11	D45281P	3			SM00003		S		YD158-YD170
0003	20	PA		4-4	23-32-11	D45281P	3			SM00003		S		YL951-YL967
0003	20	PA		7-4	23-32-11	D45281P	3			D10657A	8			YL968-YL999
0003	20	PA		2-7	44-21-12	D40011P	2			SM00011		9		YR303-YR328
0004	20	PA		4-9	23-32-11	D45281P	4			SM00004		S		YC051-YD157
0004	20	PA		7-0	23-32-11	D45281P	4			D10657A	23			YD158-YD170
0004	20	PA		7-4	23-32-11	D45281P	4			D10657A	23			YL951-YL999
0005	20	PA		6-2	23-32-11	D45281P	5			SM00005		S		YC051-YD157
0005	20	PA		7-0	23-32-11	D45281P	5			SM00005		S		YD158-YD170
0005	20	PA		7-5	23-32-11	D45281P	5			SM00005		S		YL951-YL999
0005	20	PA		2-7	44-21-12	D40011P	4			SM00009		9		YR303-YR328
0006	20	PA		3-10	23-32-11	D10673	1			SM00001		S		YC051-YC052
0006	20	PA		3-10	23-32-11	D10673	1			SM00020		S		YC053-YC058
0007	20	PA		3-10	23-32-11	D10673	3			SM00002		S		YC051-YC058
0008	22	PA		1-0	23-32-11	D10673	7			SM00005		S		YC051-YD157
0008	22	PA		1-0	23-32-11	D10657B	106			SM00005		S		YD158-YL999
0009	20	PA		3-10	23-32-11	D10673	5			SM00003		S		YC051-YD157
0009	20	PA		3-8	23-32-11	SM00003			S	D10657A	8			YD158-YD170
0010	20	PA		3-10	23-32-11	D10673	6			SM00004		S		YC051-YD157
0010	20	PA		3-10	23-32-11	SM00003			S	D10657A	8			YL951-YL967
0011	20	PA		1-6	23-32-11	D10659	1			SM00001		S		YC051-YC052
0011	20	PA		1-6	23-32-11	D10659	1			SM00020		S		YC053-YC058
0012	20	PA		1-6	23-32-11	D10659	2			SM00002		S		YC051-YC058
0013	20	PA		3-4	23-32-11	D10659	5			SM00005		S		YC051-YD157
0013	20	PA		6-1	23-32-11	D10659	5			SM00005		S		YD158-YD170
0013	20	PA		6-7	23-32-11	D10659	5			SM00005		S		YL951-YL999
0014	20	PA		1-7	23-32-11	D10661	1			SM00001		S		YC051-YC052
0014	20	PA		1-7	23-32-11	D10661	1			SM00020		S		YC053-YC058
0015	20	PA		1-7	23-32-11	D10661	2			SM00002		S		YC051-YC058

WIRE LIST

D280A108

91-21-11

Section W3590

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3599	286A3599				VIDEO - VIDEO CONTROL CENTER - GALLEY G7 (continued)										
0016	20		PA		3-11	23-32-11	D10661		5		SM00005		S		YC051-YD157
0016	20		PA		6-7	23-32-11	D10661		5		SM00005		S		YD158-YD170
001CO				CA	0-0	23-32-13	D10667		= 1		D10659		= 30		YC051-YD157
001CO				JA	0-0	23-32-21	D45287P		= C15		D10657A		= C31		YD158-YD170
001CO				IA	0-0	23-32-21	D45287P		= 15		D10657A		= C31		YL951-YL999
001CX			OF	CA	4-4	23-32-13	D10667		1		D10659		30		YC051-YD157
001CX			OF	JA	6-4	23-32-21	D45287P		15		D10657A		31		YD158-YD170
001CX			OF	IA	6-7	23-32-21	D45287P		15		D10657A		31		YL951-YL999
0021	22		PA		6-8	23-32-12	D45283P		20		D10673		20		YC051-YD157
0021	22		PA		6-7	23-32-14	D45283P		20		D10657B		41		YD158-YD170
0021	22		PA		7-0	23-32-14	D45283P		20		D10657B		41		YL951-YL999
0022	22		CQ		6-8	23-32-12	D45283P		21		D10673		26		YC051-YD157
0022	22		CQ		6-7	23-32-14	D45283P		21		D10657A		19		YD158-YD170
0022	22		CQ		7-0	23-32-14	D45283P		21		D10657A		19		YL951-YL999
0023	22		PA		6-8	23-32-12	D45283P		1		D10673		27		YC051-YD157
0023	22		PA		6-7	23-32-12	D45283P		1		D10657A		20		YD158-YD170
0023	22		PA		7-0	23-32-12	D45283P		30		D10657A		20		YL951-YL999
0024	22		PA		6-8	23-32-12	D45283P		28		D10673		14		YC051-YD157
0024	22		PA		6-8	23-32-12	D45283P		28		D10657C		34		YD158-YD170
0024	22		PA		7-1	23-32-12	D45283P		28		D10657C		34		YL951-YL999
0025	22		PA		6-8	23-32-12	D45283P		29		D10673		15		YC051-YD157
0026	22		PA		6-7	23-32-12	D45283P		30		D10673		CAP	Y	YC051-YD157
0027	22		PA		3-10	23-32-13	D10673		38		SM00020			S	YC051-YC052
0027	22		PA		3-10	23-32-13	D10673		38		SM00001			S	YC053-YD157
0027	22		PA		3-8	23-32-21	SM00020			S	D10657A		7		YD158-YD170
0027	20		PA		1-1	23-32-21	D10657A		7		SM00005			S	YL951-YL999
0028	22		PA		1-6	23-32-13	D10659		6		SM00020			S	YC051-YC052
0028	22		PA		1-6	23-32-13	D10659		6		SM00001			S	YC053-YD157
0028	24		PK		6-1	23-32-13	D10657A		1		D10659		27		YD158-YD170
0028	22		PA		6-6	23-32-13	D10657A		1		D10659		27		YL951-YL999
0029	22		PA		1-6	23-32-13	D10659		7		SM00020			S	YC051-YC052
0029	22		PA		1-6	23-32-13	D10659		7		SM00001			S	YC053-YD157
0029	24		PK		6-7	23-32-13	D10657A		2		D10661		27		YD158-YD170
002CO				CB	0-0	23-32-13	D10667		= 2		D10661		= 30		YC051-YD157
002CX			OF	CB	4-11	23-32-13	D10667		2		D10661		30		YC051-YD157
0030	20		PA		3-8	23-32-13	D10657B			AC	SM00020			S	YD158-YD170
0030	20		PA		7-5	23-32-13	D10657B			AC	D45281P		31		YL951-YL999
0031	20		PA		3-8	23-32-13	D10657B			AD	SM00020			S	YD158-YD170
0034	20		PA		4-6	23-32-21	D45287P		1		SM00003			S	YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W3590

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3599		286A3599			VIDEO - VIDEO CONTROL CENTER - GALLEY G7 (continued)											
0034		20		PA		3-11	23-32-21	D45287P		1		SM00003		S		YD158-YD170
0034		20		PA		4-1	23-32-21	D45287P		16		SM00003		S		YL951-YL967
0035		20		PA		1-6	23-32-11	D10659		3		SM00003		S		YC051-YD157
0036		20		PA		1-6	23-32-11	D10659		4		SM00004		S		YC051-YD157
0037		20		PA		1-7	23-32-11	D10661		3		SM00003		S		YC051-YD157
0038		20		PA		1-7	23-32-11	D10661		4		SM00004		S		YC051-YD157
0039		18		PA		6-7	23-32-12	D45283P		36	18	D10673	CAP	Y		YC051-YD157
0040		20		PA		6-7	23-32-12	D45283P		37		D10673	CAP	Y		YC051-YD157
0041		22		PA		6-7	23-32-12	D45283P		38		D10673	CAP	Y		YC051-YD157
0041		22		PA		6-7	23-32-14	D45283P		38		D10657B		30		YD158-YD170
0041		22		PA		7-0	23-32-14	D45283P		38		D10657B		30		YL951-YL999
0042		22		PA		6-8	23-32-12	D45283P		34		D10673		31		YC051-YD157
0042		22		PA		6-7	23-32-14	D45283P		34		D10657B		31		YD158-YD170
0042		22		PA		7-0	23-32-14	D45283P		34		D10657B		31		YL951-YL999
0043		22		PA		6-7	23-32-12	D45283P		35		D10673	CAP	Y		YC051-YD157
0043		22		PA		6-7	23-32-14	D45283P		35		D10657B		32		YD158-YD170
0043		22		PA		7-0	23-32-14	D45283P		35		D10657B		32		YL951-YL999
0044		22		PA		1-7	23-32-13	D10661		6		SM00020		S		YC051-YC052
0044		22		PA		1-7	23-32-13	D10661		6		SM00001		S		YC053-YD157
0045		22		PA		1-7	23-32-13	D10661		7		SM00020		S		YC051-YC052
0045		22		PA		1-7	23-32-13	D10661		7		SM00001		S		YC053-YD157
0051		20		PA		8-5	23-32-33	D10001P		1		D10333		1		YC051-YD157
0052		20		PA		8-5	23-32-33	D10001P		2		D10333		4		YC051-YD157
0053		22		PA		8-5	23-32-33	D10001P		10		D10333		2		YC051-YD157
0054		24		PK		8-5	23-32-33	D10001P		6		D10333		8		YC051-YD157
0055		22		PA		8-5	23-32-33	D10001P		9		D10333		3		YC051-YD157
0057		22		PA		8-5	23-32-33	D10001P		4		D10333		5		YC051-YD157
0058		22		PA		8-5	23-32-33	D10001P		7		D10333		6		YC051-YD157
0059		22		PA		8-5	23-32-33	D10001P		8		D10333		7		YC051-YD157
0066		20		PA		4-2	23-32-13	D45281P		31		SM00020		S		YD158-YD170
0085		20		PA		3-6	44-21-12	DB13357		10		SM00013		9		YR303-YR328
0086		20		PA		3-6	44-21-12	DB13357		14		SM00013		9		YR303-YR328
0087		20		PA		3-6	44-21-12	DB13357		9		SM00011		9		YR303-YR328
0088		20		PA		3-6	44-21-12	DB13357		13		SM00011		9		YR303-YR328
0089		22		PA		6-7	23-32-14	D45283P		46		D10657B		33		YD158-YD170
0089		22		PA		7-0	23-32-14	D45283P		46		D10657B		33		YL951-YL999
0091		20		PA		3-6	44-21-12	DB13357		21		SM00009		9		YR303-YR328
0092		20		PA		3-6	44-21-12	DB13357		22		SM00009		9		YR303-YR328
011CO					CC	0-0	23-32-33	D10003P		=C1		D10333		=C1		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W3590

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3599	286A3599				VIDEO - VIDEO CONTROL CENTER - GALLEY G7 (continued)										
011CX			0F	CC	8-0	23-32-33	D10003P	= A1			D10333	= A1			YC051-YD157
2001B	22		PB	BF	6-10	23-32-21	D45287P	9			SM00031		S		YD158-YD170
2001R	22		PB	BF	0-0	23-32-21	D45287P	8			SM00030		S		YD158-YD170
2002B	20		PB	DA	4-9	23-32-11	D45281P	2			SM00002		S		YC059-YD157
2002B	22		PB	BG	0-7	23-32-21	D10657B	37			SM00031		S		YD158-YD170
2002R	20		PB	DA	0-0	23-32-11	D45281P	1			SM00020		S		YC059-YD157
2002R	22		PB	BG	0-0	23-32-21	D10657B	36			SM00030		S		YD158-YD170
2003B	20		PB	DB	3-10	23-32-11	D10673	1			SM00020		S		YC059-YD157
2003B	22		PB	BH	0-7	23-32-21	D10657B	39			SM00031		S		YD158-YD170
2003R	20		PB	DB	0-0	23-32-11	D10673	3			SM00002		S		YC059-YD157
2003R	22		PB	BH	0-0	23-32-21	D10657B	38			SM00030		S		YD158-YD170
2004B	20		PB	DC	1-6	23-32-11	D10659	2			SM00002		S		YC059-YD157
2004R	20		PB	DC	0-0	23-32-11	D10659	1			SM00020		S		YC059-YD157
2005B	20		PB	DD	1-7	23-32-11	D10661	2			SM00002		S		YC059-YD157
2005R	20		PB	DD	0-0	23-32-11	D10661	1			SM00020		S		YC059-YD157
2008B	20		PB	BK	4-2	23-32-11	D45281P	2			SM00002		S		YD158-YD170
2008B	20		PB	AI	4-4	23-32-11	D45281P	2			SM00002		S		YL951-YL999
2008R	20		PB	BK	0-0	23-32-11	D45281P	1			SM00001		S		YD158-YD170
2008R	20		PB	AI	0-0	23-32-11	D45281P	1			SM00001		S		YL951-YL999
2009B	20		PB	BL	3-8	23-32-11	D10657C	5			SM00002		S		YD158-YD170
2009B	20		PB	AV	3-11	23-32-11	D10657C	5			SM00002		S		YL951-YL999
2009R	20		PB	BL	0-0	23-32-11	D10657C	3			SM00001		S		YD158-YD170
2009R	20		PB	AV	0-0	23-32-11	D10657C	3			SM00001		S		YL951-YL999
2010B	20		PB	BM	2-6	23-32-11	D10659	4			SM00002		S		YD158-YD170
2010B	20		PB	BH	2-9	23-32-11	D10659	4			SM00002		S		YL951-YL999
2010R	20		PB	BM	0-0	23-32-11	D10659	3			SM00001		S		YD158-YD170
2010R	20		PB	BH	0-0	23-32-11	D10659	3			SM00001		S		YL951-YL999
2011B	20		PB	BN	3-0	23-32-11	D10661	4			SM00002		S		YD158-YD170
2011R	20		PB	BN	0-0	23-32-11	D10661	3			SM00001		S		YD158-YD170
2501B	22		X2	AA	7-0	23-32-12	D45283P	6			D10669	29			YC051-YD157
2501B	22		X2	AA	6-8	23-32-12	D45283P	6			D10657C	60			YD158-YD170
2501B	22		X2	AA	7-1	23-32-12	D45283P	6			D10657C	60			YL951-YL999
2501R	22		X2	AA	0-0	23-32-12	D45283P	5			D10669	28			YC051-YD157
2501R	22		X2	AA	0-0	23-32-12	D45283P	5			D10657C	61			YD158-YL999
2501Z				AA	0-0	23-32-12	D45283P		AA		D10669			AB	YC051-YD157
2501Z				AA	0-0	23-32-12	D45283P		AE		D10657C	DED			YD158-YL999
2502B	22		X2	AB	7-0	23-32-12	D45283P	8			D10669	31			YC051-YD157
2502B	22		X2	AB	6-8	23-32-12	D45283P	8			D10657C	58			YD158-YD170
2502B	22		X2	AB	7-1	23-32-12	D45283P	8			D10657C	58			YL951-YL999

WIRE LIST

D280A108

91-21-11

Section W3590

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3599	286A3599			VIDEO - VIDEO CONTROL CENTER - GALLEY G7 (continued)											
2502R	22		X2	AB	0-0	23-32-12	D45283P	7			D10669	30			YC051-YD157
2502R	22		X2	AB	0-0	23-32-12	D45283P	7			D10657C	59			YD158-YL999
2502Z				AB	0-0	23-32-12	D45283P			AA	D10669			AB	YC051-YD157
2502Z				AB	0-0	23-32-12	D45283P			AE	D10657C	DED			YD158-YL999
2503B	22		X2	AC	7-0	23-32-12	D45283P	11			D10669	33			YC051-YD157
2503B	22		X2	AC	6-8	23-32-12	D45283P	11			D10657C	53			YD158-YD170
2503B	22		X2	AC	7-1	23-32-12	D45283P	10			D10657C	47			YL951-YL999
2503R	22		X2	AC	0-0	23-32-12	D45283P	10			D10669	32			YC051-YD157
2503R	22		X2	AC	0-0	23-32-12	D45283P	10			D10657C	54			YD158-YD170
2503R	22		X2	AC	0-0	23-32-12	D45283P	9			D10657C	48			YL951-YL999
2503Z				AC	0-0	23-32-12	D45283P			AC	D10669			AB	YC051-YD157
2503Z				AC	0-0	23-32-12	D45283P			AG	D10657C	DED			YD158-YD170
2503Z				AC	0-0	23-32-12	D45283P			AE	D10657C	DED			YL951-YL999
2504B	22		X2	AD	7-0	23-32-12	D45283P	13			D10669	36			YC051-YD157
2504B	22		X2	AD	6-8	23-32-12	D45283P	13			D10657C	51			YD158-YD170
2504B	22		X2	AD	7-1	23-32-12	D45283P	13			D10657C	53			YL951-YL999
2504R	22		X2	AD	0-0	23-32-12	D45283P	12			D10669	35			YC051-YD157
2504R	22		X2	AD	0-0	23-32-12	D45283P	12			D10657C	52			YD158-YD170
2504R	22		X2	AD	0-0	23-32-12	D45283P	12			D10657C	54			YL951-YL999
2504Z				AD	0-0	23-32-12	D45283P			AC	D10669			AD	YC051-YD157
2504Z				AD	0-0	23-32-12	D45283P			AG	D10657C	DED			YD158-YD170
2504Z				AD	0-0	23-32-12	D45283P			AF	D10657C	DED			YL951-YL999
2505B	22		X2	AE	7-0	23-32-12	D45283P	16			D10669	38			YC051-YD157
2505B	22		X2	AE	6-8	23-32-12	D45283P	16			D10657C	47			YD158-YD170
2505B	22		X2	AE	7-1	23-32-12	D45283P	15			D10657C	51			YL951-YL999
2505R	22		X2	AE	0-0	23-32-12	D45283P	15			D10669	37			YC051-YD157
2505R	22		X2	AE	0-0	23-32-12	D45283P	15			D10657C	48			YD158-YD170
2505R	22		X2	AE	0-0	23-32-12	D45283P	14			D10657C	52			YL951-YL999
2505Z				AE	0-0	23-32-12	D45283P			AE	D10669			AD	YC051-YD157
2505Z				AE	0-0	23-32-12	D45283P			AJ	D10657C	DED			YD158-YD170
2505Z				AE	0-0	23-32-12	D45283P			AF	D10657C	DED			YL951-YL999
2506B	22		X2	AF	7-0	23-32-12	D45283P	18			D10669	40			YC051-YD157
2506B	22		X2	AF	6-8	23-32-12	D45283P	18			D10657C	45			YD158-YD170
2506B	22		X2	AF	7-1	23-32-12	D45283P	17			D10657C	45			YL951-YL999
2506R	22		X2	AF	0-0	23-32-12	D45283P	17			D10669	39			YC051-YD157
2506R	22		X2	AF	0-0	23-32-12	D45283P	17			D10657C	46			YD158-YD170
2506R	22		X2	AF	0-0	23-32-12	D45283P	16			D10657C	46			YL951-YL999
2506Z				AF	0-0	23-32-12	D45283P			AE	D10669			AD	YC051-YD157
2506Z				AF	0-0	23-32-12	D45283P			AJ	D10657C	DED			YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W3590

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3599	286A3599				VIDEO - VIDEO CONTROL CENTER - GALLEY G7 (continued)											
2506Z				AF	0-0	23-32-12		D45283P				AF	D10657C	DED		YL951-YL999
2507B	22	X2		AG	7-0	23-32-12		D45283P	3				D10669	22		YC051-YD157
2507B	22	X2		AG	6-8	23-32-12		D45283P	3				D10657C	56		YD158-YD170
2507B	22	X2		AG	7-1	23-32-12		D45283P	3				D10657C	56		YL951-YL999
2507R	22	X2		AG	0-0	23-32-12		D45283P	2				D10669	21		YC051-YD157
2507R	22	X2		AG	0-0	23-32-12		D45283P	2				D10657C	57		YD158-YD999
2507Z				AG	0-0	23-32-12		D45283P				AF	D10669		AG	YC051-YD157
2507Z				AG	0-0	23-32-12		D45283P	4				D10657C	35		YD158-YL999
2508B	22	X2		AH	7-0	23-32-12		D45283P	25				D10669	24		YC051-YD157
2508R	22	X2		AH	0-0	23-32-12		D45283P	24				D10669	23		YC051-YD157
2508Z				AH	0-0	23-32-12		D45283P				AF	D10669		AG	YC051-YD157
2509B	24	OT		AI	7-2	23-32-12		D45283P	27				D10675	10		YC051-YD157
2509W	24	OT		AI	0-0	23-32-12		D45283P	26				D10675	9		YC051-YD157
2509Z				AI	0-0	23-32-12		D45283P	4				D10675	8		YC051-YD157
2510B	22	X2		AJ	4-5	23-32-13		D10671	3				D10659	11		YC051-YD157
2510B	24	Y2		AJ	6-1	23-32-13		D10657B	12				D10659	31		YD158-YD170
2510B	24	Y2		AK	6-7	23-32-13		D10657B	12				D10659	31		YL951-YL999
2510R	22	X2		AJ	0-0	23-32-13		D10671	2				D10659	10		YC051-YD157
2510R	24	Y2		AJ	0-0	23-32-13		D10657B	11				D10659	30		YD158-YD170
2510R	24	Y2		AK	0-0	23-32-13		D10657B	11				D10659	30		YL951-YL999
2510Z				AJ	0-0	23-32-13		D10671				AH	D10659		AI	YC051-YD157
2510Z				AJ	0-0	23-32-13		D10657B	DED				D10659	18		YD158-YD170
2510Z				AK	0-0	23-32-13		D10657B	DED				D10659	18		YL951-YL999
2511B	22	X2		AK	4-5	23-32-13		D10671	5				D10659	13		YC051-YD157
2511B	24	Y2		AK	6-1	23-32-13		D10657B	14				D10659	33		YD158-YD170
2511B	24	Y2		AL	6-7	23-32-13		D10657B	14				D10659	33		YL951-YL999
2511R	22	X2		AK	0-0	23-32-13		D10671	4				D10659	12		YC051-YD157
2511R	24	Y2		AK	0-0	23-32-13		D10657B	13				D10659	32		YD158-YD170
2511R	24	Y2		AL	0-0	23-32-13		D10657B	13				D10659	32		YL951-YL999
2511Z				AK	0-0	23-32-13		D10671				AH	D10659		AI	YC051-YD157
2511Z				AK	0-0	23-32-13		D10657B	DED				D10659	20		YD158-YD170
2511Z				AL	0-0	23-32-13		D10657B	DED				D10659	20		YL951-YL999
2512B	22	X2		AL	4-5	23-32-13		D10671	7				D10659	15		YC051-YD157
2512B	24	Y2		AL	6-1	23-32-13		D10657B	10				D10659	64		YD158-YD170
2512B	24	Y2		AM	6-7	23-32-13		D10657B	10				D10659	64		YL951-YL999
2512R	22	X2		AL	0-0	23-32-13		D10671	6				D10659	14		YC051-YD157
2512R	24	Y2		AL	0-0	23-32-13		D10657B	9				D10659	63		YD158-YD170
2512R	24	Y2		AM	0-0	23-32-13		D10657B	9				D10659	63		YL951-YL999
2512Z				AL	0-0	23-32-13		D10671				AH	D10659		AI	YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W3590

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To							
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice
W3599	286A3599			VIDEO - VIDEO CONTROL CENTER - GALLEY G7 (continued)											
2512Z				AL	0-0	23-32-13	D10657B	DED			D10659	51			YD158-YD170
2512Z				AM	0-0	23-32-13	D10657B	DED			D10659	51			YL951-YL999
2513B	24		OT	AM	4-9	23-32-13	D10675	2			D10659	20			YC051-YD157
2513B	24		OT	AM	6-1	23-32-13	D10657B	56			D10659	53			YD158-YD170
2513B	24		OT	AN	6-7	23-32-13	D10657B	56			D10659	53			YL951-YL999
2513W	24		OT	AM	0-0	23-32-13	D10675	1			D10659	19			YC051-YD157
2513W	24		OT	AM	0-0	23-32-13	D10657B	55			D10659	54			YD158-YD170
2513W	24		OT	AN	0-0	23-32-13	D10657B	55			D10659	54			YL951-YL999
2513Z				AM	0-0	23-32-13	D10675			AJ	D10659	21			YC051-YD157
2513Z				AM	0-0	23-32-13	D10657B			AC	D10659	66			YD158-YD170
2513Z				AN	0-0	23-32-13	D10657B			AC	D10659	66			YL951-YL999
2514B	22		X2	AN	5-1	23-32-13	D10671	10			D10661	11			YC051-YD157
2514B	24		Y2	AN	6-7	23-32-13	D10657B	19			D10661	31			YD158-YD170
2514R	22		X2	AN	0-0	23-32-13	D10671	9			D10661	10			YC051-YD157
2514R	24		Y2	AN	0-0	23-32-13	D10657B	18			D10661	30			YD158-YD170
2514Z				AN	0-0	23-32-13	D10671			AK	D10661			AL	YC051-YD157
2514Z				AN	0-0	23-32-13	D10657B	DED			D10661	18			YD158-YD170
2515B	22		X2	AP	5-1	23-32-13	D10671	12			D10661	13			YC051-YD157
2515B	24		Y2	AP	6-7	23-32-13	D10657B	21			D10661	33			YD158-YD170
2515R	22		X2	AP	0-0	23-32-13	D10671	11			D10661	12			YC051-YD157
2515R	24		Y2	AP	0-0	23-32-13	D10657B	20			D10661	32			YD158-YD170
2515Z				AP	0-0	23-32-13	D10671			AK	D10661			AL	YC051-YD157
2515Z				AP	0-0	23-32-13	D10657B	DED			D10661	20			YD158-YD170
2516B	22		X2	AQ	5-1	23-32-13	D10671	14			D10661	15			YC051-YD157
2516B	24		Y2	AQ	6-7	23-32-13	D10657B	17			D10661	64			YD158-YD170
2516R	22		X2	AQ	0-0	23-32-13	D10671	13			D10661	14			YC051-YD157
2516R	24		Y2	AQ	0-0	23-32-13	D10657B	16			D10661	63			YD158-YD170
2516Z				AQ	0-0	23-32-13	D10671			AK	D10661			AL	YC051-YD157
2516Z				AQ	0-0	23-32-13	D10657B	DED			D10661	51			YD158-YD170
2517B	24		OT	AR	5-4	23-32-13	D10675	5			D10661	20			YC051-YD157
2517B	24		OT	AR	6-7	23-32-13	D10657B	58			D10661	53			YD158-YD170
2517W	24		OT	AR	0-0	23-32-13	D10675	4			D10661	19			YC051-YD157
2517W	24		OT	AR	0-0	23-32-13	D10657B	57			D10661	54			YD158-YD170
2517Z				AR	0-0	23-32-13	D10675			AJ	D10661	21			YC051-YD157
2517Z				AR	0-0	23-32-13	D10657B			AD	D10661	66			YD158-YD170
2518B	24		OT	AS	7-4	23-32-21	D45287P	3			D10675	20			YC051-YD157
2518B	24		OT	AS	6-10	23-32-21	D45287P	3			D10657B	88			YD158-YD170
2518B	24		OT	AT	7-2	23-32-21	D45287P	3			D10657B	88			YL951-YL999
2518W	24		OT	AS	0-0	23-32-21	D45287P	2			D10675	19			YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W3590

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3599	286A3599			VIDEO - VIDEO CONTROL CENTER - GALLEY G7 (continued)											
2518W	24	OT	AS		0-0	23-32-21	D45287P		2		D10657B	87			YD158-YD170
2518W	24	OT	AT		0-0	23-32-21	D45287P		2		D10657B	87			YL951-YL999
2518Z			AS		0-0	23-32-21	D45287P		4		D10675		AM		YC051-YD157
2518Z			AS		0-0	23-32-21	D45287P		4		D10657B	89			YD158-YD170
2518Z			AT		0-0	23-32-21	D45287P		4		D10657B	89			YL951-YL999
2519B	24	7P	AT		7-1	23-32-21	D45287P		5		D10671	53			YC051-YD157
2519BN	24	7P	AT		0-0	23-32-21	D45287P		6		D10671	54			YC051-YD157
2519Z			AT		0-0	23-32-21	D45287P		7		D10671	52			YC051-YD157
2520B	24	Y2	BH		7-1	23-32-21	D10671		45		D45287P	9			YC051-YD157
2520R	24	Y2	BH		0-0	23-32-21	D10671		44		D45287P	8			YC051-YD157
2520Z			BH		0-0	23-32-21	D10671		43		D45287P	10			YC051-YD157
2521B	24	OT	AV		7-7	23-32-31	D45281P		7		D10675	15			YC051-YD157
2521B	24	OT	AV		7-0	23-32-31	D45281P		7		D10657A	14			YD158-YD170
2521B	24	OT	AZ		7-4	23-32-31	D45281P		7		D10657A	14			YL951-YL999
2521W	24	OT	AV		0-0	23-32-31	D45281P		6		D10675	14			YC051-YD157
2521W	24	OT	AV		0-0	23-32-31	D45281P		6		D10657A	13			YD158-YD170
2521W	24	OT	AZ		0-0	23-32-31	D45281P		6		D10657A	13			YL951-YL999
2521Z			AV		0-0	23-32-31	D45281P		8		D10675	7			YC051-YD157
2521Z			AV		0-0	23-32-31	D45281P		8		D10657A	15			YD158-YD170
2521Z			AZ		0-0	23-32-31	D45281P		8		D10657A	15			YL951-YL999
2522B	24	7P	AW		7-5	23-32-31	D45281P		9		D10669	2			YC051-YD157
2522B	24	7P	AW		7-0	23-32-31	D45281P		9		D10657B	65			YD158-YD170
2522B	24	7P	BA		7-5	23-32-31	D45281P		9		D10657B	65			YL951-YL999
2522BN	24	7P	AW		0-0	23-32-31	D45281P		10		D10669	3			YC051-YD157
2522BN	24	7P	AW		0-0	23-32-31	D45281P		10		D10657B	66			YD158-YD170
2522BN	24	7P	BA		0-0	23-32-31	D45281P		10		D10657B	66			YL951-YL999
2522Z			AW		0-0	23-32-31	D45281P		11		D10669	1			YC051-YD157
2522Z			AW		0-0	23-32-31	D45281P		11		D10657B	67			YD158-YD170
2522Z			BA		0-0	23-32-31	D45281P		11		D10657B	67			YL951-YL999
2523B	24	7P	AX		7-5	23-32-31	D45281P		12		D10669	5			YC051-YD157
2523B	24	7P	AX		7-0	23-32-31	D45281P		12		D10657B	73			YD158-YD170
2523B	24	7P	BB		7-5	23-32-31	D45281P		12		D10657B	73			YL951-YL999
2523BN	24	7P	AX		0-0	23-32-31	D45281P		13		D10669	6			YC051-YD157
2523BN	24	7P	AX		0-0	23-32-31	D45281P		13		D10657B	74			YD158-YD170
2523BN	24	7P	BB		0-0	23-32-31	D45281P		13		D10657B	74			YL951-YL999
2523Z			AX		0-0	23-32-31	D45281P		14		D10669	4			YC051-YD157
2523Z			AX		0-0	23-32-31	D45281P		14		D10657B	75			YD158-YD170
2523Z			BB		0-0	23-32-31	D45281P		14		D10657B	75			YL951-YL999
2524B	24	7P	AY		7-5	23-32-31	D45281P		15		D10669	8			YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W3590

Page 9

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice
W3599	286A3599			VIDEO - VIDEO CONTROL CENTER - GALLEY G7 (continued)											
2524B	24	7P	AY	7-0	23-32-31	D45281P		15		D10657B	80		YD158-YD170		
2524B	24	7P	BC	7-5	23-32-31	D45281P		15		D10657B	80		YL951-YL999		
2524BN	24	7P	AY	0-0	23-32-31	D45281P		16		D10669	9		YC051-YD157		
2524BN	24	7P	AY	0-0	23-32-31	D45281P		16		D10657B	81		YD158-YD170		
2524BN	24	7P	BC	0-0	23-32-31	D45281P		16		D10657B	81		YL951-YL999		
2524Z			AY	0-0	23-32-31	D45281P		17		D10669	7		YC051-YD157		
2524Z			AY	0-0	23-32-31	D45281P		17		D10657B	82		YD158-YD170		
2524Z			BC	0-0	23-32-31	D45281P		17		D10657B	82		YL951-YL999		
2525B	24	0T	AZ	7-7	23-32-51	D45281P		19		D10675	17		YC051-YD157		
2525B	24	0T	AZ	7-0	23-32-51	D45281P		19		D10657A	17		YD158-YD170		
2525B	24	0T	BD	7-4	23-32-51	D45281P		19		D10657A	17		YL951-YL999		
2525W	24	0T	AZ	0-0	23-32-51	D45281P		18		D10675	16		YC051-YD157		
2525W	24	0T	AZ	0-0	23-32-51	D45281P		18		D10657A	16		YD158-YD170		
2525W	24	0T	BD	0-0	23-32-51	D45281P		18		D10657A	16		YL951-YL999		
2525Z			AZ	0-0	23-32-51	D45281P		20		D10675		AM	YC051-YD157		
2525Z			AZ	0-0	23-32-51	D45281P		20		D10657A	18		YD158-YD170		
2525Z			BD	0-0	23-32-51	D45281P		20		D10657A	18		YL951-YL999		
2526B	24	7P	BA	7-5	23-32-51	D45281P		21		D10669	11		YC051-YD157		
2526B	24	7P	BA	7-0	23-32-51	D45281P		21		D10657B	68		YD158-YD170		
2526B	24	7P	BE	7-5	23-32-51	D45281P		21		D10657B	68		YL951-YL999		
2526BN	24	7P	BA	0-0	23-32-51	D45281P		22		D10669	12		YC051-YD157		
2526BN	24	7P	BA	0-0	23-32-51	D45281P		22		D10657B	69		YD158-YD170		
2526BN	24	7P	BE	0-0	23-32-51	D45281P		22		D10657B	69		YL951-YL999		
2526Z			BA	0-0	23-32-51	D45281P		23		D10669	10		YC051-YD157		
2526Z			BA	0-0	23-32-51	D45281P		23		D10657B	70		YD158-YD170		
2526Z			BE	0-0	23-32-51	D45281P		23		D10657B	70		YL951-YL999		
2527B	24	7P	BB	7-5	23-32-51	D45281P		24		D10669	14		YC051-YD157		
2527B	24	7P	BB	7-0	23-32-51	D45281P		24		D10657B	76		YD158-YD170		
2527B	24	7P	BF	7-5	23-32-51	D45281P		24		D10657B	76		YL951-YL999		
2527BN	24	7P	BB	0-0	23-32-51	D45281P		25		D10669	15		YC051-YD157		
2527BN	24	7P	BB	0-0	23-32-51	D45281P		25		D10657B	77		YD158-YD170		
2527BN	24	7P	BF	0-0	23-32-51	D45281P		25		D10657B	77		YL951-YL999		
2527Z			BB	0-0	23-32-51	D45281P		26		D10669	13		YC051-YD157		
2527Z			BB	0-0	23-32-51	D45281P		26		D10657B	78		YD158-YD170		
2527Z			BF	0-0	23-32-51	D45281P		26		D10657B	78		YL951-YL999		
2528B	24	7P	BC	7-5	23-32-51	D45281P		27		D10669	17		YC051-YD157		
2528B	24	7P	BC	7-0	23-32-51	D45281P		27		D10657B	83		YD158-YD170		
2528B	24	7P	BG	7-5	23-32-51	D45281P		27		D10657B	83		YL951-YL999		
2528BN	24	7P	BC	0-0	23-32-51	D45281P		28		D10669	18		YC051-YD157		

WIRE LIST

D280A108

91-21-11

Section W3590

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3599	286A3599				VIDEO - VIDEO CONTROL CENTER - GALLEY G7 (continued)										
2528BN	24		7P	BC	0-0	23-32-51	D45281P	28			D10657B	84			YD158-YD170
2528BN	24		7P	BG	0-0	23-32-51	D45281P	28			D10657B	84			YL951-YL999
2528Z				BC	0-0	23-32-51	D45281P	29			D10669	16			YC051-YD157
2528Z				BC	0-0	23-32-51	D45281P	29			D10657B	85			YD158-YD170
2528Z				BG	0-0	23-32-51	D45281P	29			D10657B	85			YL951-YL999
2529B	24		0T	BD	7-2	23-32-12	D45283P	32			D10675	12			YC051-YD157
2529W	24		0T	BD	0-0	23-32-12	D45283P	31			D10675	11			YC051-YD157
2529Z				BD	0-0	23-32-12	D45283P	33			D10675	13			YC051-YD157
2531B	24		Y2	BK	7-2	23-32-21	D45287P	9			D10657B	37			YL951-YL999
2531R	24		Y2	BK	0-0	23-32-21	D45287P	8			D10657B	36			YL951-YL999
2531Z				BK	0-0	23-32-21	D45287P	10			D10657B	DED			YL951-YL999
2532B	24		Y2	BL	7-2	23-32-21	D45287P	18			D10657B	39			YL951-YL999
2532R	24		Y2	BL	0-0	23-32-21	D45287P	17			D10657B	38			YL951-YL999
2532Z				BL	0-0	23-32-21	D45287P	25			D10657B	DED			YL951-YL999
2534B	24		Y2	AI	6-1	23-32-13	D10659	35			D10657B	27			YD158-YD170
2534R	24		Y2	AI	0-0	23-32-13	D10659	34			D10657B	26			YD158-YD170
2534Z				AI	0-0	23-32-13	D10659	22			D10657B	DED			YD158-YD170
2535B	24		Y2	AH	6-7	23-32-13	D10657B	29			D10661	35			YD158-YD170
2535R	24		Y2	AH	0-0	23-32-13	D10657B	28			D10661	34			YD158-YD170
2535Z				AH	0-0	23-32-13	D10657B	DED			D10661	22			YD158-YD170
3001B	22		PC	GA	6-7	23-32-12	D45283P	32			D10657A	26			YD158-YD170
3001B	22		PC	GA	7-0	23-32-12	D45283P	32			D10657A	26			YL951-YL999
3001R	22		PC	GA	0-0	23-32-12	D45283P	31			D10657A	25			YD158-YL999
3001Y	22		PC	GA	0-0	23-32-12	D45283P	33			D10657A	27			YD158-YL999
4001B	24		FS	KA	6-5	44-21-12	D12897P	A-4			DA13357	1-3			YR303-YR328
4001G	24		FS	KA	0-0	44-21-12	D12897P	A-3			DA13357	1-4			YR303-YR328
4001R	24		FS	KA	0-0	44-21-12	D12897P	A-2			DA13357	1-1			YR303-YR328
4001Y	24		FS	KA	0-0	44-21-12	D12897P	A-1			DA13357	1-2			YR303-YR328
4001Z				KA	0-0	44-21-12	D12897P	=CA			DA13357	=C1			YR303-YR328
4002B	24		FS	KB	6-5	44-21-12	D12897P	B-4			DA13357	3-3			YR303-YR328
4002G	24		FS	KB	0-0	44-21-12	D12897P	B-3			DA13357	3-4			YR303-YR328
4002R	24		FS	KB	0-0	44-21-12	D12897P	B-2			DA13357	3-1			YR303-YR328
4002Y	24		FS	KB	0-0	44-21-12	D12897P	B-1			DA13357	3-2			YR303-YR328
4002Z				KB	0-0	44-21-12	D12897P	=CB			DA13357	=C3			YR303-YR328
4003B	24		FS	KC	6-3	44-21-12	D45449P	A-3			DA13357	2-3			YR303-YR328
4003G	24		FS	KC	0-0	44-21-12	D45449P	A-4			DA13357	2-4			YR303-YR328
4003R	24		FS	KC	0-0	44-21-12	D45449P	A-1			DA13357	2-1			YR303-YR328
4003Y	24		FS	KC	0-0	44-21-12	D45449P	A-2			DA13357	2-2			YR303-YR328
4003Z				KC	0-0	44-21-12	D45449P	=CA			DA13357	=C2			YR303-YR328

WIRE LIST

D280A108

91-21-11

Section W3590

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3599 286A3599 VIDEO - VIDEO CONTROL CENTER - GALLEY G7 (continued)																
4004B		24		FS	KD	6-3	44-21-12	D45449P		B-3		DA13357		4-3		YR303-YR328
4004G		24		FS	KD	0-0	44-21-12	D45449P		B-4		DA13357		4-4		YR303-YR328
4004R		24		FS	KD	0-0	44-21-12	D45449P		B-1		DA13357		4-1		YR303-YR328
4004Y		24		FS	KD	0-0	44-21-12	D45449P		B-2		DA13357		4-2		YR303-YR328
4004Z					KD	0-0	44-21-12	D45449P		=CB		DA13357		=C4		YR303-YR328
FRAA						0-0	23-32-12	D45283P			AA	D45283P		9		YC051-YD157
FRAB						0-0	23-32-12	D10669			AB	D10669		27		YC051-YD157
FRAC						0-0	23-32-12	D45283P			AC	D45283P		14		YC051-YD157
FRAD						0-0	23-32-12	D10669			AD	D10669		34		YC051-YD157
FRAE						0-0	23-32-12	D45283P			AE	D45283P		19		YC051-YD157
FRAE						0-0	23-32-12	D45283P			AE	D45283P		9		YD158-YD170
FRAE						0-0	23-32-12	D45283P			AE	D45283P		11		YL951-YL999
FRAF						0-0	23-32-12	D45283P			AF	D45283P		39		YC051-YD157
FRAF						0-0	23-32-12	D45283P			AF	D45283P		18		YL951-YL999
FRAG						0-0	23-32-12	D10669			AG	D10669		20		YC051-YD157
FRAG						0-0	23-32-12	D45283P			AG	D45283P		14		YD158-YD170
FRAH						0-0	23-32-13	D10671			AH	D10671		1		YC051-YD157
FRAI						0-0	23-32-13	D10659			AI	D10659		18		YC051-YD157
FRAJ						0-0	23-32-13	D10675			AJ	D10675		3		YC051-YD157
FRAJ						0-0	23-32-12	D45283P			AJ	D45283P		19		YD158-YD170
FRAK						0-0	23-32-13	D10671			AK	D10671		8		YC051-YD157
FRAL						0-0	23-32-13	D10661			AL	D10661		18		YC051-YD157
FRAM						0-0	23-32-21	D10675			AM	D10675		18		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W3590

Page 12 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3605	286A3605				VIDEO - P6 TO VDU TRAYS & DISC BRKT STA 691, TO VDU TRAYS 1 & 4										
0001	20		PA		56-11	23-32-11	D45233P		2		D45275J		1		YL951-YL999
0001	20		PA		45-9	23-32-11	D45233P		2		D45275J		1		YN231-YN260
0002	20		PA		1-11	23-32-31	SM00001		REF	AA	GD03860	ST..	1		YL951-YN260
0003	20		PA		2-5	23-32-31	SM00001			S	D10201		11		YL951-YN260
0004	20		PA		2-5	23-32-31	SM00002			S	D10201		12		YL951-YN260
0005	20		PA		2-8	23-32-31	GD03860		ST..	1	D10201		13		YL951-YN260
0006	20		PA		2-8	23-32-31	GD03860		ST..	1	D10201		19		YL951-YN260
0007	20		PA		3-9	23-32-41	GD08012		ST..	1	SM00003	REF		AB	YL951-YL999
0007	20		PA		4-6	23-32-41	GD03742		ST..	1	SM00003	REF		AB	YN231-YN260
0008	20		PA		2-6	23-32-41	SM00003			S	D10233		11		YL951-YN260
0009	20		PA		2-6	23-32-41	SM00004			S	D10233		12		YL951-YN260
0010	20		PA		6-2	23-32-41	GD08012		ST..	1	D10233		13		YL951-YL999
0010	20		PA		5-1	23-32-41	GD03742		ST..	1	D10233		13		YN231-YN260
0011	20		PA		6-2	23-32-41	GD08012		ST..	1	D10233		19		YL951-YL999
0011	20		PA		5-1	23-32-41	GD03742		ST..	1	D10233		19		YN231-YN260
0012	20		PA		3-0	23-32-51	GD04004		ST..	1	SM00005	REF		AC	YL951-YN260
0013	20		PA		1-11	23-32-51	SM00005			S	D10265		11		YL951-YN260
0014	20		PA		1-11	23-32-51	SM00006			S	D10265		12		YL951-YN260
0015	20		PA		3-8	23-32-51	GD04004		ST..	1	D10265		13		YL951-YN260
0016	20		PA		3-8	23-32-51	GD04004		ST..	1	D10265		19		YL951-YN260
0017	20		PA		1-11	23-32-61	SM00007		REF		GD08028	ST..	1		YL951-YL999
0017	20		PA		2-1	23-32-61	SM00007		REF	AD	GD03764	ST..	1		YN231-YN260
0018	20		PA		2-1	23-32-61	SM00007			S	D10297		11		YL951-YN260
0019	20		PA		2-1	23-32-61	SM00008			S	D10297		12		YL951-YN260
0020	20		PA		3-5	23-32-61	GD08028		ST..	1	D10297		13		YL951-YL999
0020	20		PA		3-9	23-32-61	GD03764		ST..	1	D10297		13		YN231-YN260
0021	20		PA		3-5	23-32-61	GD08028		ST..	1	D10297		19		YL951-YL999
0021	20		PA		3-9	23-32-61	GD03764		ST..	1	D10297		19		YN231-YN260
2001B	20		PB	EA	56-11	23-32-11	D45233P			15	D45275J		3		YL951-YL999
2001B	20		PB	EA	45-9	23-32-11	D45233P			15	D45275J		3		YN231-YN260
2001R	20		PB	EA	0-0	23-32-11	D45233P			14	D45275J		2		YL951-YN260
2501B	18		X2	AA	17-10	23-32-31	D45233P			4	SM00002			S	YL951-YN260
2501R	18		X2	AA	0-0	23-32-31	D45233P			3	SM00001			S	YL951-YN260
2501Z				AA	0-0	23-32-31	D45233P		DED		SM00001	REF		AA	YL951-YN260
2502B	24		OT	AB	40-5	23-32-31	D45275J			7	D10201		8		YL951-YL999
2502B	24		OT	AB	29-9	23-32-31	D45275J			7	D10201		8		YN231-YN260
2502W	24		OT	AB	0-0	23-32-31	D45275J			6	D10201		7		YL951-YN260
2502Z				AB	0-0	23-32-31	D45275J			8	D10201		9		YL951-YN260
2503B	24		7P	AC	40-5	23-32-31	D45275J			9	D10201		1		YL951-YL999

WIRE LIST

D280A108

91-21-11

Section W3600

Page 1

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3605 286A3605 VIDEO - P6 TO VDU TRAYS & DISC BRKT STA 691, TO VDU TRAYS 1 & 4 (continued)																
2503B		24		7P	AC	29-9	23-32-31	D45275J		9		D10201		1		YN231-YN260
2503BN		24		7P	AC	0-0	23-32-31	D45275J		10		D10201		2		YL951-YN260
2503Z					AC	0-0	23-32-31	D45275J		11		D10201		3		YL951-YN260
2504B		24		7P	AD	40-5	23-32-31	D45275J		12		D10201		4		YL951-YL999
2504B		24		7P	AD	29-9	23-32-31	D45275J		12		D10201		4		YN231-YN260
2504BN		24		7P	AD	0-0	23-32-31	D45275J		13		D10201		5		YL951-YN260
2504Z					AD	0-0	23-32-31	D45275J		14		D10201		6		YL951-YN260
2505B		24		7P	AE	40-5	23-32-31	D45275J		15		D10201		14		YL951-YL999
2505B		24		7P	AE	29-9	23-32-31	D45275J		15		D10201		14		YN231-YN260
2505BN		24		7P	AE	0-0	23-32-31	D45275J		16		D10201		15		YL951-YN260
2505Z					AE	0-0	23-32-31	D45275J		17		D10201		16		YL951-YN260
2506B		18		X2	AF	34-6	23-32-41	D45233P		6	18	SM00004			S	YL951-YL999
2506B		18		X2	AF	32-9	23-32-41	D45233P		6	18	SM00004			S	YN231-YN260
2506R		18		X2	AF	0-0	23-32-41	D45233P		5	18	SM00003			S	YL951-YN260
2506Z					AF	0-0	23-32-41	D45233P	DED			SM00003	REF			AB
2507B		24		0T	AG	20-11	23-32-41	D10227		8		D10233		8		YL951-YL999
2507B		24		0T	AG	19-0	23-32-41	D10227		8		D10233		8		YN231-YN260
2507W		24		0T	AG	0-0	23-32-41	D10227		7		D10233		7		YL951-YN260
2507Z					AG	0-0	23-32-41	D10227		9		D10233		9		YL951-YN260
2508B		24		7P	AH	20-11	23-32-41	D10227		1		D10233		1		YL951-YL999
2508B		24		7P	AH	19-0	23-32-41	D10227		1		D10233		1		YN231-YN260
2508BN		24		7P	AH	0-0	23-32-41	D10227		2		D10233		2		YL951-YN260
2508Z					AH	0-0	23-32-41	D10227		3		D10233		3		YL951-YN260
2509B		24		7P	AI	20-11	23-32-41	D10227		4		D10233		4		YL951-YL999
2509B		24		7P	AI	19-0	23-32-41	D10227		4		D10233		4		YN231-YN260
2509BN		24		7P	AI	0-0	23-32-41	D10227		5		D10233		5		YL951-YN260
2509Z					AI	0-0	23-32-41	D10227		6		D10233		6		YL951-YN260
2510B		24		7P	AJ	20-11	23-32-41	D10227		14		D10233		14		YL951-YL999
2510B		24		7P	AJ	19-0	23-32-41	D10227		14		D10233		14		YN231-YN260
2510BN		24		7P	AJ	0-0	23-32-41	D10227		15		D10233		15		YL951-YN260
2510Z					AJ	0-0	23-32-41	D10227		16		D10233		16		YL951-YN260
2511B		18		X2	AK	55-1	23-32-51	D45233P		8	18	SM00006			S	YL951-YL999
2511B		18		X2	AK	47-0	23-32-51	D45233P		8	18	SM00006			S	YN231-YN260
2511R		18		X2	AK	0-0	23-32-51	D45233P		7	18	SM00005			S	YL951-YN260
2511Z					AK	0-0	23-32-51	D45233P	DED			SM00005	REF			AC
2512B		24		0T	AL	3-1	23-32-51	D45275J		19		D10265		8		YL951-YL999
2512B		24		0T	AL	3-8	23-32-51	D45275J		19		D10265		8		YN231-YN260
2512W		24		0T	AL	0-0	23-32-51	D45275J		18		D10265		7		YL951-YN260
2512Z					AL	0-0	23-32-51	D45275J		20		D10265		9		YL951-YN260

WIRE LIST

D280A108

91-21-11

Section W3600

Page 2

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3605	286A3605				VIDEO - P6 TO VDU TRAYS & DISC BRKT STA 691, TO VDU TRAYS 1 & 4 (continued)										
2513B	24		7P	AM	3-1	23-32-51	D45275J	21			D10265	1			YL951-YL999
2513B	24		7P	AM	3-8	23-32-51	D45275J	21			D10265	1			YN231-YN260
2513BN	24		7P	AM	0-0	23-32-51	D45275J	22			D10265	2			YL951-YN260
2513Z				AM	0-0	23-32-51	D45275J	23			D10265	3			YL951-YN260
2514B	24		7P	AN	3-1	23-32-51	D45275J	24			D10265	4			YL951-YL999
2514B	24		7P	AN	3-8	23-32-51	D45275J	24			D10265	4			YN231-YN260
2514BN	24		7P	AN	0-0	23-32-51	D45275J	25			D10265	5			YL951-YN260
2514Z				AN	0-0	23-32-51	D45275J	26			D10265	6			YL951-YN260
2515B	24		7P	AP	3-1	23-32-51	D45275J	27			D10265	14			YL951-YL999
2515B	24		7P	AP	3-8	23-32-51	D45275J	27			D10265	14			YN231-YN260
2515BN	24		7P	AP	0-0	23-32-51	D45275J	28			D10265	15			YL951-YN260
2515Z				AP	0-0	23-32-51	D45275J	29			D10265	16			YL951-YN260
2516B	18		X2	AQ	76-4	23-32-61	D45233P	10	18		SM00008		S		YL951-YL999
2516B	18		X2	AQ	60-5	23-32-61	D45233P	10	18		SM00008		S		YN231-YN260
2516R	18		X2	AQ	0-0	23-32-61	D45233P	9	18		SM00007		S		YL951-YN260
2516Z				AQ	0-0	23-32-61	D45233P	DED			SM00007	REF		AD	YL951-YN260
2517B	24		0T	AR	25-4	23-32-61	D10283	8			D10297	8			YL951-YL999
2517B	24		0T	AR	18-10	23-32-61	D10283	8			D10297	8			YN231-YN260
2517W	24		0T	AR	0-0	23-32-61	D10283	7			D10297	7			YL951-YN260
2517Z				AR	0-0	23-32-61	D10283	9			D10297	9			YL951-YN260
2518B	24		7P	AS	25-4	23-32-61	D10283	1			D10297	1			YL951-YL999
2518B	24		7P	AS	18-10	23-32-61	D10283	1			D10297	1			YN231-YN260
2518BN	24		7P	AS	0-0	23-32-61	D10283	2			D10297	2			YL951-YN260
2518Z				AS	0-0	23-32-61	D10283	3			D10297	3			YL951-YN260
2519B	24		7P	AT	25-4	23-32-61	D10283	4			D10297	4			YL951-YL999
2519B	24		7P	AT	18-10	23-32-61	D10283	4			D10297	4			YN231-YN260
2519BN	24		7P	AT	0-0	23-32-61	D10283	5			D10297	5			YL951-YN260
2519Z				AT	0-0	23-32-61	D10283	6			D10297	6			YL951-YN260
2520B	24		7P	AU	25-4	23-32-61	D10283	14			D10297	14			YL951-YL999
2520B	24		7P	AU	18-10	23-32-61	D10283	14			D10297	14			YN231-YN260
2520BN	24		7P	AU	0-0	23-32-61	D10283	15			D10297	15			YL951-YN260
2520Z				AU	0-0	23-32-61	D10283	16			D10297	16			YL951-YN260
W3607	286A3607				GPS ANT-1										
001CO				AA	0-0	34-58-11	D02941	= C1			D42941J	= C1			ALL
001CX			0F	AA	39-11	34-58-11	D02941	= A1			D42941J	= A1			YC051-YC055
001CX			0F	AA	40-3	34-58-11	D02941	= A1			D42941J	= A1			YC056-YL999, YR301-YR328
001CX			0F	AA	40-0	34-58-11	D02941	= A1			D42941J	= A1			YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W3600

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I	W3609	286A3609			GPS ANT-2											
I	001CO				AA	0-0	34-58-21	D02947	= C1			D42943J	= C1			ALL
I	001CX			0F	AA	36-8	34-58-21	D02947	= A1			D42943J	= A1			YC051-YL999, YR301-YR328
	001CX			0F	AA	36-7	34-58-21	D02947	= A1			D42943J	= A1			YN231-YN501

For training purposes only!

WIRE LIST

D280A108

91-21-11

Section W3600

Page 4 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3653	286A3653				VIDEO CONTROL CENTER - GALLEY G3 (STA 916-940)										
0003	20		PA		6-6	23-32-11	D45139P		3		SM00004		S		YN231-YN235
0003	20		PA		6-10	23-32-11	D45139P		3		D10657A	8			YN236-YN260
0004	20		PA		6-6	23-32-11	D45139P		4		SM00003		S		YN231-YN235
0004	20		PA		6-10	23-32-11	D45139P		4		D10657A	23			YN236-YN260
0005	20		PA		6-5	23-32-11	D45139P		5		SM00005		S		YN231-YN260
0008	22		PA		1-0	23-32-11	D10657B		106		SM00005		S		YN231-YN260
0009	20		PA		0-11	23-32-11	SM00003			S	D10657A	23			YN231-YN235
0010	20		PA		0-11	23-32-11	D10657A		8		SM00004		S		YN231-YN235
0013	20		PA		3-6	23-32-11	D10659		5		SM00005		S		YN231-YN260
001CO				IA	0-0	23-32-21	D10657A	= C31			D45145P	= 15			YN231-YN260
001CX				IA	6-2	23-32-21	D10657A		31		D45145P	15			YN231-YN260
0021	22		PA		6-7	23-32-14	D45129P		20		D10657B	41			YN231-YN260
0022	22		CQ		6-8	23-32-14	D45129P		21		D10657A	19			YN231-YN260
0023	22		PA		6-8	23-32-12	D45129P		30		D10657A	20			YN231-YN260
0024	22		PA		6-7	23-32-12	D45129P		28		D10657C	34			YN231-YN260
0027	20		PA		0-11	23-32-21	D10657A		7		SM00003		S		YN231-YN235
0027	20		PA		1-5	23-32-21	D10657A		7		SM00005		S		YN236-YN260
0028	22		PA		3-11	23-32-13	D10657A		1		D10659	27			YN231-YN260
0030	20		PA		6-9	23-32-13	D10657B			AC	D45139P	31			YN231-YN260
0034	20		PA		6-4	23-32-21	D45145P		16		SM00004		S		YN231-YN235
0041	22		PA		6-7	23-32-14	D45129P		38		D10657B	30			YN231-YN260
0042	22		PA		6-7	23-32-14	D45129P		34		D10657B	31			YN231-YN260
0043	22		PA		6-7	23-32-14	D45129P		35		D10657B	32			YN231-YN260
0089	22		PA		6-7	23-32-14	D45129P		46		D10657B	33			YN231-YN260
2008B	20		PB	BK	6-5	23-32-11	D45139P		2		SM00002		S		YN231-YN260
2008R	20		PB	BK	0-0	23-32-11	D45139P		1		SM00001		S		YN231-YN260
2009B	20		PB	BL	0-10	23-32-11	D10657C		5		SM00002		S		YN231-YN260
2009R	20		PB	BL	0-0	23-32-11	D10657C		3		SM00001		S		YN231-YN260
2010B	20		PB	BM	3-5	23-32-11	D10659		4		SM00002		S		YN231-YN260
2010R	20		PB	BM	0-0	23-32-11	D10659		3		SM00001		S		YN231-YN260
2501B	22		X2	AA	6-7	23-32-12	D45129P		6		D10657C	60			YN231-YN260
2501R	22		X2	AA	0-0	23-32-12	D45129P		5		D10657C	61			YN231-YN260
2501Z				AA	0-0	23-32-12	D45129P			AE	D10657C	DED			YN231-YN260
2502B	22		X2	AB	6-7	23-32-12	D45129P		8		D10657C	58			YN231-YN260
2502R	22		X2	AB	0-0	23-32-12	D45129P		7		D10657C	59			YN231-YN260
2502Z				AB	0-0	23-32-12	D45129P			AE	D10657C	DED			YN231-YN260
2503B	22		X2	AC	6-7	23-32-12	D45129P		10		D10657C	47			YN231-YN260
2503R	22		X2	AC	0-0	23-32-12	D45129P		9		D10657C	48			YN231-YN260
2503Z				AC	0-0	23-32-12	D45129P			AE	D10657C	DED			YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W3650

Page 1

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Diagram	From	To								
	Wire No.	GA	CO TY			Fam	FT-IN	Equip	Term	Type	Splice	Equip	Term	Type	Splice
W3653	286A3653			VIDEO CONTROL CENTER - GALLEY G3 (STA 916-940) (continued)											
2504B	22	X2	AD		6-7	23-32-12	D45129P	13			D10657C	53			YN231-YN260
2504R	22	X2	AD		0-0	23-32-12	D45129P	12			D10657C	54			YN231-YN260
2504Z			AD		0-0	23-32-12	D45129P			AF	D10657C	DED			YN231-YN260
2505B	22	X2	AE		6-7	23-32-12	D45129P	15			D10657C	51			YN231-YN260
2505R	22	X2	AE		0-0	23-32-12	D45129P	14			D10657C	52			YN231-YN260
2505Z			AE		0-0	23-32-12	D45129P			AF	D10657C	DED			YN231-YN260
2506B	22	X2	AF		6-7	23-32-12	D45129P	17			D10657C	45			YN231-YN260
2506R	22	X2	AF		0-0	23-32-12	D45129P	16			D10657C	46			YN231-YN260
2506Z			AF		0-0	23-32-12	D45129P			AF	D10657C	DED			YN231-YN260
2507B	22	X2	AG		6-7	23-32-12	D45129P	3			D10657C	56			YN231-YN260
2507R	22	X2	AG		0-0	23-32-12	D45129P	2			D10657C	57			YN231-YN260
2507Z			AG		0-0	23-32-12	D45129P	4			D10657C	35			YN231-YN260
2510B	24	Y2	AJ		3-10	23-32-13	D10657B	12			D10659	31			YN231-YN260
2510R	24	Y2	AJ		0-0	23-32-13	D10657B	11			D10659	30			YN231-YN260
2510Z			AJ		0-0	23-32-13	D10657B		DED		D10659	18			YN231-YN260
2511B	24	Y2	AK		3-10	23-32-13	D10657B	14			D10659	33			YN231-YN260
2511R	24	Y2	AK		0-0	23-32-13	D10657B	13			D10659	32			YN231-YN260
2511Z			AK		0-0	23-32-13	D10657B		DED		D10659	20			YN231-YN260
2512B	24	Y2	AL		3-10	23-32-13	D10657B	10			D10659	64			YN231-YN260
2512R	24	Y2	AL		0-0	23-32-13	D10657B	9			D10659	63			YN231-YN260
2512Z			AL		0-0	23-32-13	D10657B		DED		D10659	51			YN231-YN260
2513B	24	OT	AM		3-10	23-32-13	D10657B	56			D10659	53			YN231-YN260
2513W	24	OT	AM		0-0	23-32-13	D10657B	55			D10659	54			YN231-YN260
2513Z			AM		0-0	23-32-13	D10657B			AC	D10659	66			YN231-YN260
2521B	24	OT	AV		6-10	23-32-31	D45139P	7			D10657A	14			YN231-YN260
2521W	24	OT	AV		0-0	23-32-31	D45139P	6			D10657A	13			YN231-YN260
2521Z			AV		0-0	23-32-31	D45139P	8			D10657A	15			YN231-YN260
2522B	24	7P	AW		6-9	23-32-31	D45139P	9			D10657B	65			YN231-YN260
2522BN	24	7P	AW		0-0	23-32-31	D45139P	10			D10657B	66			YN231-YN260
2522Z			AW		0-0	23-32-31	D45139P	11			D10657B	67			YN231-YN260
2523B	24	7P	AX		6-9	23-32-31	D45139P	12			D10657B	73			YN231-YN260
2523BN	24	7P	AX		0-0	23-32-31	D45139P	13			D10657B	74			YN231-YN260
2523Z			AX		0-0	23-32-31	D45139P	14			D10657B	75			YN231-YN260
2524B	24	7P	AY		6-9	23-32-31	D45139P	15			D10657B	80			YN231-YN260
2524BN	24	7P	AY		0-0	23-32-31	D45139P	16			D10657B	81			YN231-YN260
2524Z			AY		0-0	23-32-31	D45139P	17			D10657B	82			YN231-YN260
2525B	24	OT	AZ		6-10	23-32-51	D45139P	19			D10657A	17			YN231-YN260
2525W	24	OT	AZ		0-0	23-32-51	D45139P	18			D10657A	16			YN231-YN260
2525Z			AZ		0-0	23-32-51	D45139P	20			D10657A	18			YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W3650

Page 2

Aug 14/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3653	286A3653			VIDEO CONTROL CENTER - GALLEY G3 (STA 916-940) (continued)											
2526B	24		7P	BA	6-9	23-32-51	D45139P	21			D10657B	68			YN231-YN260
2526BN	24		7P	BA	0-0	23-32-51	D45139P	22			D10657B	69			YN231-YN260
2526Z				BA	0-0	23-32-51	D45139P	23			D10657B	70			YN231-YN260
2527B	24		7P	BB	6-9	23-32-51	D45139P	24			D10657B	76			YN231-YN260
2527BN	24		7P	BB	0-0	23-32-51	D45139P	25			D10657B	77			YN231-YN260
2527Z				BB	0-0	23-32-51	D45139P	26			D10657B	78			YN231-YN260
2528B	24		7P	BC	6-9	23-32-51	D45139P	27			D10657B	83			YN231-YN260
2528BN	24		7P	BC	0-0	23-32-51	D45139P	28			D10657B	84			YN231-YN260
2528Z				BC	0-0	23-32-51	D45139P	29			D10657B	85			YN231-YN260
2531B	24		Y2	BF	6-7	23-32-21	D45145P	9			D10657B	37			YN231-YN260
2531R	24		Y2	BF	0-0	23-32-21	D45145P	8			D10657B	36			YN231-YN260
2531Z				BF	0-0	23-32-21	D45145P	10			D10657B	DED			YN231-YN260
2532B	24		Y2	BG	6-7	23-32-21	D45145P	18			D10657B	39			YN231-YN260
2532R	24		Y2	BG	0-0	23-32-21	D45145P	17			D10657B	38			YN231-YN260
2532Z				BG	0-0	23-32-21	D45145P	25			D10657B	DED			YN231-YN260
2533B	24		0T	BH	6-7	23-32-21	D10657B	88			D45145P	3			YN231-YN260
2533W	24		0T	BH	0-0	23-32-21	D10657B	87			D45145P	2			YN231-YN260
2533Z				BH	0-0	23-32-21	D10657B	89			D45145P	4			YN231-YN260
2534B	24		Y2	BI	3-10	23-32-13	D10657B	27			D10659	35			YN231-YN260
2534R	24		Y2	BI	0-0	23-32-13	D10657B	26			D10659	34			YN231-YN260
2534Z				BI	0-0	23-32-13	D10657B	DED			D10659	22			YN231-YN260
3001B	22		PC	GA	6-8	23-32-12	D45129P	32			D10657A	26			YN231-YN260
3001R	22		PC	GA	0-0	23-32-12	D45129P	31			D10657A	25			YN231-YN260
3001Y	22		PC	GA	0-0	23-32-12	D45129P	33			D10657A	27			YN231-YN260
FRAE					0-0	23-32-12	D45129P			AE	D45129P	11			YN231-YN260
FRAF					0-0	23-32-12	D45129P			AF	D45129P	18			YN231-YN260
W3657	286A3657			IFE - (BSI) SERVER BASED SYSTEM PSU - OVERHEAD VIDEO LEFT FORWARD											
0001	18		PA		10-7	44-21-36	D41052P	A			D12955	9	18		YN501-YR328
0002	18		PA		10-7	44-21-36	D41052P	B			D12955	10	18		YN501-YR328
0003	20		PA		10-7	44-21-36	D41052P	C			D12955	11			YN501-YR328
0004	20		PA		10-9	44-21-36	D45421P	3			D12955	3			YN501-YR328
0005	18		PA		20-6	44-21-36	D12971	9	18		D12959	9	18		YN501-YR328
0006	18		CQ		20-6	44-21-36	D12971	10	18		D12959	10	18		YN501-YR328
0007	18		PA		20-6	44-21-36	D12971	11	18		D12959	11	18		YN501-YR328
0008	18		PA		20-6	44-21-36	D12971	3	18		D12959	3	18		YN501-YR328
0009	18		PA		22-1	44-21-36	D12987	9	18		D12975	9	18		YN501
0009	18		PA		24-0	44-21-36	D12987	9	18		D12975	9	18		YR301-YR328
0010	18		CQ		22-1	44-21-36	D12987	10	18		D12975	10	18		YN501

WIRE LIST

D280A108

91-21-11

Section W3650

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Diagram	From				To				Effectivity		
	Wire No.	GA	CO TY			Fam	FT-IN	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W3657	286A3657					IFE - (BSI) SERVER BASED SYSTEM PSU - OVERHEAD VIDEO LEFT FORWARD (continued)										
0010	18	CQ			24-0	44-21-36	D12987	10	18			D12975	10	18		YR301-YR328
0011	18	PA			22-1	44-21-36	D12987	11	18			D12975	11	18		YN501
0011	18	PA			24-0	44-21-36	D12987	11	18			D12975	11	18		YR301-YR328
0012	18	PA			22-1	44-21-36	D12987	3	18			D12975	3	18		YN501
0012	18	PA			24-0	44-21-36	D12987	3	18			D12975	3	18		YR301-YR328
0013	18	PA			17-6	44-21-36	D13005	3	18			D12991	3	18		YN501
0013	18	PA			18-0	44-21-36	D13005	3	18			D12991	3	18		YR301-YR328
0014	18	PA			17-6	44-21-36	D13005	11	18			D12991	11	18		YN501
0014	18	PA			18-0	44-21-36	D13005	11	18			D12991	11	18		YR301-YR328
0015	18	CQ			17-6	44-21-36	D13005	10	18			D12991	10	18		YN501
0015	18	CQ			18-0	44-21-36	D13005	10	18			D12991	10	18		YR301-YR328
0016	18	PA			17-6	44-21-36	D13005	9	18			D12991	9	18		YN501
0016	18	PA			18-0	44-21-36	D13005	9	18			D12991	9	18		YR301-YR328
0017	18	PA			18-0	44-21-36	D13021	3	18			D13009	3	18		YR301-YR328
0018	18	PA			18-0	44-21-36	D13021	11	18			D13009	11	18		YR301-YR328
0019	18	CQ			18-0	44-21-36	D13021	10	18			D13009	10	18		YR301-YR328
0020	18	PA			18-0	44-21-36	D13021	9	18			D13009	9	18		YR301-YR328
0021	18	PA			16-1	44-21-36	GD03844	ST..	1			D13009	3	18		YN501
0021	18	PA			6-9	44-21-36	GD03742	ST..	1			D13025	3	18		YR301-YR328
2501B	20	X2	AA		10-9	44-21-36	D45421P	5				D12955	2			YN501-YR328
2501R	20	X2	AA		0-0	44-21-36	D45421P	4				D12955	1			YN501-YR328
2501Z			AA		0-0	44-21-36	D45421P	6				D12955	4			YN501-YR328
2502B	20	X2	AB		20-6	44-21-36	D12971	2				D12959	2			YN501-YR328
2502R	20	X2	AB		0-0	44-21-36	D12971	1				D12959	1			YN501-YR328
2502Z			AB		0-0	44-21-36	D12971	4				D12959	4			YN501-YR328
2503B	20	X2	AC		22-1	44-21-36	D12987	2				D12975	2			YN501
2503B	20	X2	AC		24-0	44-21-36	D12987	2				D12975	2			YR301-YR328
2503R	20	X2	AC		0-0	44-21-36	D12987	1				D12975	1			YN501-YR328
2503Z			AC		0-0	44-21-36	D12987	4				D12975	4			YN501-YR328
2504B	20	X2	AD		17-6	44-21-36	D13005	2				D12991	2			YN501
2504B	20	X2	AD		18-0	44-21-36	D13005	2				D12991	2			YR301-YR328
2504R	20	X2	AD		0-0	44-21-36	D13005	1				D12991	1			YN501-YR328
2504Z			AD		0-0	44-21-36	D13005	4				D12991	4			YN501-YR328
2505B	20	X2	AE		18-0	44-21-36	D13021	2				D13009	2			YR301-YR328
2505R	20	X2	AE		0-0	44-21-36	D13021	1				D13009	1			YR301-YR328
2505Z			AE		0-0	44-21-36	D13021	4				D13009	4			YR301-YR328
4001B	24	FS	KA		10-8	44-21-36	D45427P	A-4				D12957	A-4			YN501-YR328
4001G	24	FS	KA		0-0	44-21-36	D45427P	A-3				D12957	A-3			YN501-YR328
4001R	24	FS	KA		0-0	44-21-36	D45427P	A-2				D12957	A-2			YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W3650

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3657	286A3657			IFE - (BSI) SERVER BASED SYSTEM PSU - OVERHEAD VIDEO LEFT FORWARD (continued)											
4001Y	24	FS	KA		0-0	44-21-36	D45427P	A-1			D12957	A-1			YN501-YR328
4001Z			KA		0-0	44-21-36	D45427P	=CA			D12957	=CA			YN501-YR328
4003B	24	FS	KC		20-6	44-21-36	D12973	A-4			D12961	A-3			YN501-YR328
4003G	24	FS	KC		0-0	44-21-36	D12973	A-3			D12961	A-4			YN501-YR328
4003R	24	FS	KC		0-0	44-21-36	D12973	A-2			D12961	A-1			YN501-YR328
4003Y	24	FS	KC		0-0	44-21-36	D12973	A-1			D12961	A-2			YN501-YR328
4003Z			KC		0-0	44-21-36	D12973	=CA			D12961	=CA			YN501-YR328
4004B	24	FS	KD		22-1	44-21-36	D12989	A-4			D12977	A-3			YN501
4004B	24	FS	KD		24-0	44-21-36	D12989	A-4			D12977	A-3			YR301-YR328
4004G	24	FS	KD		0-0	44-21-36	D12989	A-3			D12977	A-4			YN501-YR328
4004R	24	FS	KD		0-0	44-21-36	D12989	A-2			D12977	A-1			YN501-YR328
4004Y	24	FS	KD		0-0	44-21-36	D12989	A-1			D12977	A-2			YN501-YR328
4004Z			KD		0-0	44-21-36	D12989	=CA			D12977	=CA			YN501-YR328
4005B	24	FS	KE		17-6	44-21-36	D13007	A-4			D12993	A-3			YN501
4005B	24	FS	KE		18-0	44-21-36	D13007	A-4			D12993	A-3			YR301-YR328
4005G	24	FS	KE		0-0	44-21-36	D13007	A-3			D12993	A-4			YN501-YR328
4005R	24	FS	KE		0-0	44-21-36	D13007	A-2			D12993	A-1			YN501-YR328
4005Y	24	FS	KE		0-0	44-21-36	D13007	A-1			D12993	A-2			YN501-YR328
4005Z			KE		0-0	44-21-36	D13007	=CA			D12993	=CA			YN501-YR328
4006B	24	FS	KF		18-0	44-21-36	D13023	A-4			D13011	A-3			YR301-YR328
4006G	24	FS	KF		0-0	44-21-36	D13023	A-3			D13011	A-4			YR301-YR328
4006R	24	FS	KF		0-0	44-21-36	D13023	A-2			D13011	A-1			YR301-YR328
4006Y	24	FS	KF		0-0	44-21-36	D13023	A-1			D13011	A-2			YR301-YR328
4006Z			KF		0-0	44-21-36	D13023	=CA			D13011	=CA			YR301-YR328
W3659	286A3659			IFE - (BSI) SERVER BASED SYSTEM PSU - OVERHEAD VIDEO RIGHT FORWARD											
0001	18	PA			5-0	44-21-46	D41056P	A			D12963	9	18		YN501
0001	18	PA			6-5	44-21-46	D41056P	A			D12963	9	18		YR301-YR328
0002	18	PA			5-0	44-21-46	D41056P	B			D12963	10	18		YN501
0002	18	PA			6-5	44-21-46	D41056P	B			D12963	10	18		YR301-YR328
0003	20	PA			5-0	44-21-46	D41056P	C			D12963	11			YN501
0003	20	PA			6-5	44-21-46	D41056P	C			D12963	11			YR301-YR328
0004	20	PA			5-1	44-21-46	D45429P	3			D12963	3			YN501
0004	20	PA			6-6	44-21-46	D45429P	3			D12963	3			YR301-YR328
0005	18	PA			14-0	44-21-46	D12979	9	18		D12967	9	18		YN501
0005	18	PA			16-1	44-21-46	D12979	9	18		D12967	9	18		YR301-YR328
0006	18	CQ			14-0	44-21-46	D12979	10	18		D12967	10	18		YN501
0006	18	CQ			16-1	44-21-46	D12979	10	18		D12967	10	18		YR301-YR328
0007	18	PA			14-0	44-21-46	D12979	11	18		D12967	11	18		YN501

WIRE LIST

D280A108

91-21-11

Section W3650

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram									
W3659	286A3659			IFE - (BSI) SERVER BASED SYSTEM PSU - OVERHEAD VIDEO RIGHT FORWARD (continued)											
0007	18		PA		16-1	44-21-46	D12979	11	18		D12967	11	18		YR301-YR328
0008	18		PA		14-0	44-21-46	D12979	3	18		D12967	3	18		YN501
0008	18		PA		16-1	44-21-46	D12979	3	18		D12967	3	18		YR301-YR328
0009	18		PA		21-1	44-21-46	D12995	9	18		D12983	9	18		YN501
0009	18		PA		24-0	44-21-46	D12995	9	18		D12983	9	18		YR301-YR328
0010	18		CQ		21-1	44-21-46	D12995	10	18		D12983	10	18		YN501
0010	18		CQ		24-0	44-21-46	D12995	10	18		D12983	10	18		YR301-YR328
0011	18		PA		21-1	44-21-46	D12995	11	18		D12983	11	18		YN501
0011	18		PA		24-0	44-21-46	D12995	11	18		D12983	11	18		YR301-YR328
0012	18		PA		21-1	44-21-46	D12995	3	18		D12983	3	18		YN501
0012	18		PA		24-0	44-21-46	D12995	3	18		D12983	3	18		YR301-YR328
0013	18		PA		15-9	44-21-46	D13013	3	18		D12999	3	18		YN501
0013	18		PA		18-5	44-21-46	D13013	3	18		D12999	3	18		YR301-YR328
0014	18		PA		15-9	44-21-46	D13013	11	18		D12999	11	18		YN501
0014	18		PA		18-5	44-21-46	D13013	11	18		D12999	11	18		YR301-YR328
0015	18		CQ		15-9	44-21-46	D13013	10	18		D12999	10	18		YN501
0015	18		CQ		18-5	44-21-46	D13013	10	18		D12999	10	18		YR301-YR328
0016	18		PA		15-9	44-21-46	D13013	9	18		D12999	9	18		YN501
0016	18		PA		18-5	44-21-46	D13013	9	18		D12999	9	18		YR301-YR328
0017	18		PA		18-5	44-21-46	D13029	3	18		D13017	3	18		YR301-YR328
0018	18		PA		18-5	44-21-46	D13029	11	18		D13017	11	18		YR301-YR328
0019	18		CQ		18-5	44-21-46	D13029	10	18		D13017	10	18		YR301-YR328
0020	18		PA		18-5	44-21-46	D13029	9	18		D13017	9	18		YR301-YR328
0021	18		PA		12-6	44-21-46	D13017	3	18		GD03872	ST..	1		YN501
0021	18		PA		8-2	44-21-46	D13033	3	18		GD03750	ST..	1		YR301-YR328
2501B	20		X2	AA	5-1	44-21-46	D45429P	5			D12963	2			YN501
2501B	20		X2	AA	6-6	44-21-46	D45429P	5			D12963	2			YR301-YR328
2501R	20		X2	AA	0-0	44-21-46	D45429P	4			D12963	1			YN501-YR328
2501Z				AA	0-0	44-21-46	D45429P	6			D12963	4			YN501-YR328
2502B	20		X2	AB	14-0	44-21-46	D12979	2			D12967	2			YN501
2502B	20		X2	AB	16-1	44-21-46	D12979	2			D12967	2			YR301-YR328
2502R	20		X2	AB	0-0	44-21-46	D12979	1			D12967	1			YN501-YR328
2502Z				AB	0-0	44-21-46	D12979	4			D12967	4			YN501-YR328
2503B	20		X2	AC	21-1	44-21-46	D12995	2			D12983	2			YN501
2503B	20		X2	AC	24-0	44-21-46	D12995	2			D12983	2			YR301-YR328
2503R	20		X2	AC	0-0	44-21-46	D12995	1			D12983	1			YN501-YR328
2503Z				AC	0-0	44-21-46	D12995	4			D12983	4			YN501-YR328
2504B	20		X2	AD	15-9	44-21-46	D13013	2			D12999	2			YN501
2504B	20		X2	AD	18-5	44-21-46	D13013	2			D12999	2			YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3650

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3659	286A3659				IFE - (BSI) SERVER BASED SYSTEM PSU - OVERHEAD VIDEO RIGHT FORWARD (continued)										
2504R	20	X2		AD	0-0	44-21-46	D13013		1		D12999		1		YN501-YR328
2504Z				AD	0-0	44-21-46	D13013		4		D12999		4		YN501-YR328
2505B	20	X2		AE	18-5	44-21-46	D13029		2		D13017		2		YR301-YR328
2505R	20	X2		AE	0-0	44-21-46	D13029		1		D13017		1		YR301-YR328
2505Z				AE	0-0	44-21-46	D13029		4		D13017		4		YR301-YR328
4001B	24	FS		KA	4-10	44-21-46	D45435P		A-4		D12965		A-4		YN501
4001B	24	FS		KA	6-3	44-21-46	D45435P		A-4		D12965		A-4		YR301-YR328
4001G	24	FS		KA	0-0	44-21-46	D45435P		A-3		D12965		A-3		YN501-YR328
4001R	24	FS		KA	0-0	44-21-46	D45435P		A-2		D12965		A-2		YN501-YR328
4001Y	24	FS		KA	0-0	44-21-46	D45435P		A-1		D12965		A-1		YN501-YR328
4001Z				KA	0-0	44-21-46	D45435P		=CA		D12965		=CA		YN501-YR328
4003B	24	FS		KC	14-0	44-21-46	D12981		A-4		D12969		A-3		YN501
4003B	24	FS		KC	16-1	44-21-46	D12981		A-4		D12969		A-3		YR301-YR328
4003G	24	FS		KC	0-0	44-21-46	D12981		A-3		D12969		A-4		YN501-YR328
4003R	24	FS		KC	0-0	44-21-46	D12981		A-2		D12969		A-1		YN501-YR328
4003Y	24	FS		KC	0-0	44-21-46	D12981		A-1		D12969		A-2		YN501-YR328
4003Z				KC	0-0	44-21-46	D12981		=CA		D12969		=CA		YN501-YR328
4004B	24	FS		KD	21-1	44-21-46	D12997		A-4		D12985		A-3		YN501
4004B	24	FS		KD	24-0	44-21-46	D12997		A-4		D12985		A-3		YR301-YR328
4004G	24	FS		KD	0-0	44-21-46	D12997		A-3		D12985		A-4		YN501-YR328
4004R	24	FS		KD	0-0	44-21-46	D12997		A-2		D12985		A-1		YN501-YR328
4004Y	24	FS		KD	0-0	44-21-46	D12997		A-1		D12985		A-2		YN501-YR328
4004Z				KD	0-0	44-21-46	D12997		=CA		D12985		=CA		YN501-YR328
4005B	24	FS		KE	15-9	44-21-46	D13015		A-4		D13001		A-3		YN501
4005B	24	FS		KE	18-5	44-21-46	D13015		A-4		D13001		A-3		YR301-YR328
4005G	24	FS		KE	0-0	44-21-46	D13015		A-3		D13001		A-4		YN501-YR328
4005R	24	FS		KE	0-0	44-21-46	D13015		A-2		D13001		A-1		YN501-YR328
4005Y	24	FS		KE	0-0	44-21-46	D13015		A-1		D13001		A-2		YN501-YR328
4005Z				KE	0-0	44-21-46	D13015		=CA		D13001		=CA		YN501-YR328
4006B	24	FS		KF	18-5	44-21-46	D13031		A-4		D13019		A-3		YR301-YR328
4006G	24	FS		KF	0-0	44-21-46	D13031		A-3		D13019		A-4		YR301-YR328
4006R	24	FS		KF	0-0	44-21-46	D13031		A-2		D13019		A-1		YR301-YR328
4006Y	24	FS		KF	0-0	44-21-46	D13031		A-1		D13019		A-2		YR301-YR328
4006Z				KF	0-0	44-21-46	D13031		=CA		D13019		=CA		YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3650

Page 7 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3669		286A3669			IFE - (BSI) SERVER BASED SYSTEM PSU - OVERHEAD VIDEO LEFT AFT										
0001	18	PA			7-0	44-21-37	D41054P		A		D13037	9	18		YN501
0001	18	PA			8-4	44-21-37	D41054P		A		D13037	9	18		YR301-YR328
0002	18	PA			7-0	44-21-37	D41054P		B		D13037	10	18		YN501
0002	18	PA			8-4	44-21-37	D41054P		B		D13037	10	18		YR301-YR328
0003	20	PA			7-0	44-21-37	D41054P		C		D13037	11			YN501
0003	20	PA			8-4	44-21-37	D41054P		C		D13037	11			YR301-YR328
0004	20	PA			7-1	44-21-37	D45425P		3		D13037	3			YN501
0004	20	PA			8-6	44-21-37	D45425P		3		D13037	3			YR301-YR328
0005	18	PA			15-5	44-21-37	D13041		9	18	D13053	9	18		YN501
0005	18	PA			17-0	44-21-37	D13041		9	18	D13053	9	18		YR301-YR328
0006	18	CQ			15-5	44-21-37	D13041		10	18	D13053	10	18		YN501
0006	18	CQ			17-0	44-21-37	D13041		10	18	D13053	10	18		YR301-YR328
0007	18	PA			15-5	44-21-37	D13041		11	18	D13053	11	18		YN501
0007	18	PA			17-0	44-21-37	D13041		11	18	D13053	11	18		YR301-YR328
0008	18	PA			15-5	44-21-37	D13041		3	18	D13053	3	18		YN501
0008	18	PA			17-0	44-21-37	D13041		3	18	D13053	3	18		YR301-YR328
0009	18	PA			15-6	44-21-37	D13057		9	18	D13085	9	18		YN501
0009	18	PA			23-2	44-21-37	D13057		9	18	D13085	9	18		YR301-YR328
0010	18	CQ			15-6	44-21-37	D13057		10	18	D13085	10	18		YN501
0010	18	CQ			23-2	44-21-37	D13057		10	18	D13085	10	18		YR301-YR328
0011	18	PA			15-6	44-21-37	D13057		11	18	D13085	11	18		YN501
0011	18	PA			23-2	44-21-37	D13057		11	18	D13085	11	18		YR301-YR328
0012	18	PA			15-6	44-21-37	D13057		3	18	D13085	3	18		YN501
0012	18	PA			23-2	44-21-37	D13057		3	18	D13085	3	18		YR301-YR328
0013	18	PA			16-5	44-21-37	D13089		3	18	D13101	3	18		YN501
0013	18	PA			20-3	44-21-37	D13101		3	18	D13089	3	18		YR301-YR328
0014	18	PA			16-5	44-21-37	D13089		11	18	D13101	11	18		YN501
0014	18	PA			20-3	44-21-37	D13101		11	18	D13089	11	18		YR301-YR328
0015	18	CQ			16-5	44-21-37	D13089		10	18	D13101	10	18		YN501
0015	18	CQ			20-3	44-21-37	D13101		10	18	D13089	10	18		YR301-YR328
0016	18	PA			16-5	44-21-37	D13089		9	18	D13101	9	18		YN501
0016	18	PA			20-3	44-21-37	D13101		9	18	D13089	9	18		YR301-YR328
0017	18	PA			19-2	44-21-37	D13105		3	18	D13221	3	18		YR301-YR328
0018	18	PA			19-2	44-21-37	D13105		11	18	D13221	11	18		YR301-YR328
0019	18	CQ			19-2	44-21-37	D13105		10	18	D13221	10	18		YR301-YR328
0020	18	PA			19-2	44-21-37	D13105		9	18	D13221	9	18		YR301-YR328
0021	18	PA			10-4	44-21-37	GD03990	ST..	1		D13105	3	18		YN501
0021	18	PA			17-11	44-21-37	GD03850	ST..	1		D13225	3	18		YR301-YR328
2501B	20	X2	AA		7-1	44-21-37	D45425P		5		D13037	2			YN501

WIRE LIST

D280A108

91-21-11

Section W3660

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3669	286A3669			IFE - (BSI) SERVER BASED SYSTEM PSU - OVERHEAD VIDEO LEFT AFT (continued)											
2501B	20	X2	AA		8-6	44-21-37	D45425P		5		D13037		2		YR301-YR328
2501R	20	X2	AA		0-0	44-21-37	D45425P		4		D13037		1		YN501-YR328
2501Z			AA		0-0	44-21-37	D45425P		6		D13037		4		YN501-YR328
2502B	20	X2	AB		15-5	44-21-37	D13041		2		D13053		2		YN501
2502B	20	X2	AB		17-0	44-21-37	D13041		2		D13053		2		YR301-YR328
2502R	20	X2	AB		0-0	44-21-37	D13041		1		D13053		1		YN501-YR328
2502Z			AB		0-0	44-21-37	D13041		4		D13053		4		YN501-YR328
2503B	20	X2	AC		15-6	44-21-37	D13057		2		D13085		2		YN501
2503B	20	X2	AC		23-2	44-21-37	D13057		2		D13085		2		YR301-YR328
2503R	20	X2	AC		0-0	44-21-37	D13057		1		D13085		1		YN501-YR328
2503Z			AC		0-0	44-21-37	D13057		4		D13085		4		YN501-YR328
2504B	20	X2	AD		16-5	44-21-37	D13089		2		D13101		2		YN501
2504B	20	X2	AD		20-3	44-21-37	D13101		2		D13089		2		YR301-YR328
2504R	20	X2	AD		0-0	44-21-37	D13089		1		D13101		1		YN501
2504R	20	X2	AD		0-0	44-21-37	D13101		1		D13089		1		YR301-YR328
2504Z			AD		0-0	44-21-37	D13089		4		D13101		4		YN501
2504Z			AD		0-0	44-21-37	D13101		4		D13089		4		YR301-YR328
2505B	20	X2	AE		19-2	44-21-37	D13105		2		D13221		2		YR301-YR328
2505R	20	X2	AE		0-0	44-21-37	D13105		1		D13221		1		YR301-YR328
2505Z			AE		0-0	44-21-37	D13105		4		D13221		4		YR301-YR328
4001B	24	FS	KA		24-0	44-21-37	D13011		A-3		D13039		A-4		YN501
4001B	24	FS	KA		25-6	44-21-37	D13027		A-3		D13039		A-4		YR301-YR328
4001G	24	FS	KA		0-0	44-21-37	D13011		A-4		D13039		A-3		YN501
4001G	24	FS	KA		0-0	44-21-37	D13027		A-4		D13039		A-3		YR301-YR328
4001R	24	FS	KA		0-0	44-21-37	D13011		A-1		D13039		A-2		YN501
4001R	24	FS	KA		0-0	44-21-37	D13027		A-1		D13039		A-2		YR301-YR328
4001Y	24	FS	KA		0-0	44-21-37	D13011		A-2		D13039		A-1		YN501
4001Y	24	FS	KA		0-0	44-21-37	D13027		A-2		D13039		A-1		YR301-YR328
4001Z			KA		0-0	44-21-37	D13011		=CA		D13039		=CA		YN501
4001Z			KA		0-0	44-21-37	D13027		=CA		D13039		=CA		YR301-YR328
4003B	24	FS	KC		15-5	44-21-37	D13055		A-4		D13043		A-3		YN501
4003B	24	FS	KC		17-0	44-21-37	D13055		A-4		D13043		A-3		YR301-YR328
4003G	24	FS	KC		0-0	44-21-37	D13055		A-3		D13043		A-4		YN501-YR328
4003R	24	FS	KC		0-0	44-21-37	D13055		A-2		D13043		A-1		YN501-YR328
4003Y	24	FS	KC		0-0	44-21-37	D13055		A-1		D13043		A-2		YN501-YR328
4003Z			KC		0-0	44-21-37	D13055		=CA		D13043		=CA		YN501-YR328
4004B	24	FS	KD		15-6	44-21-37	D13087		A-4		D13059		A-3		YN501
4004B	24	FS	KD		23-2	44-21-37	D13087		A-4		D13059		A-3		YR301-YR328
4004G	24	FS	KD		0-0	44-21-37	D13087		A-3		D13059		A-4		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W3660

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3669 286A3669 IFE - (BSI) SERVER BASED SYSTEM PSU - OVERHEAD VIDEO LEFT AFT (continued)																
4004R		24		FS	KD	0-0	44-21-37	D13087		A-2		D13059		A-1		YN501-YR328
4004Y		24		FS	KD	0-0	44-21-37	D13087		A-1		D13059		A-2		YN501-YR328
4004Z					KD	0-0	44-21-37	D13087		=CA		D13059		=CA		YN501-YR328
4005B		24		FS	KE	16-5	44-21-37	D13103		A-4		D13091		A-3		YN501
4005B		24		FS	KE	20-3	44-21-37	D13103		A-4		D13091		A-3		YR301-YR328
4005G		24		FS	KE	0-0	44-21-37	D13103		A-3		D13091		A-4		YN501-YR328
4005R		24		FS	KE	0-0	44-21-37	D13103		A-2		D13091		A-1		YN501-YR328
4005Y		24		FS	KE	0-0	44-21-37	D13103		A-1		D13091		A-2		YN501-YR328
4005Z					KE	0-0	44-21-37	D13103		=CA		D13091		=CA		YN501-YR328
4006B		24		FS	KF	11-8	44-21-37	D13107		A-3		D45451P		2		YN501
4006B		24		FS	KF	19-2	44-21-37	D13107		A-3		D13223		A-4		YR301-YR328
4006G		24		FS	KF	0-0	44-21-37	D13107		A-4		D45451P		4		YN501
4006G		24		FS	KF	0-0	44-21-37	D13107		A-4		D13223		A-3		YR301-YR328
4006R		24		FS	KF	0-0	44-21-37	D13107		A-1		D45451P		1		YN501
4006R		24		FS	KF	0-0	44-21-37	D13107		A-1		D13223		A-2		YR301-YR328
4006Y		24		FS	KF	0-0	44-21-37	D13107		A-2		D45451P		3		YN501
4006Y		24		FS	KF	0-0	44-21-37	D13107		A-2		D13223		A-1		YR301-YR328
4006Z					KF	0-0	44-21-37	D13107		=CA		D45451P		PERB		YN501
4006Z					KF	0-0	44-21-37	D13107		=CA		D13223		=CA		YR301-YR328
4007B		24		FS	KG	13-5	44-21-37	D13227		A-3		D45451P		2		YR301-YR328
4007G		24		FS	KG	0-0	44-21-37	D13227		A-4		D45451P		4		YR301-YR328
4007R		24		FS	KG	0-0	44-21-37	D13227		A-1		D45451P		1		YR301-YR328
4007Y		24		FS	KG	0-0	44-21-37	D13227		A-2		D45451P		3		YR301-YR328
4007Z					KG	0-0	44-21-37	D13227		=CA		D45451P		PERB		YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W3660

Page 3 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To				Effectivity	
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W3671	286A3671				IFE - (BSI) SERVER BASED SYSTEM PSU - OVERHEAD VIDEO RIGHT AFT											
0001	18	PA			7-2	44-21-47	D41058P		A			D13045	9	18		YN501
0001	18	PA			8-7	44-21-47	D41058P		A			D13045	9	18		YR301-YR328
0002	18	PA			7-2	44-21-47	D41058P		B			D13045	10	18		YN501
0002	18	PA			8-7	44-21-47	D41058P		B			D13045	10	18		YR301-YR328
0003	20	PA			7-2	44-21-47	D41058P		C			D13045	11			YN501
0003	20	PA			8-7	44-21-47	D41058P		C			D13045	11			YR301-YR328
0004	20	PA			7-0	44-21-47	D45433P		3			D13045	3			YN501
0004	20	PA			8-6	44-21-47	D45433P		3			D13045	3			YR301-YR328
0005	18	PA			15-5	44-21-47	D13061		9	18		D13049	9	18		YN501
0005	18	PA			16-11	44-21-47	D13061		9	18		D13049	9	18		YR301-YR328
0006	18	CQ			15-5	44-21-47	D13061		10	18		D13049	10	18		YN501
0006	18	CQ			16-11	44-21-47	D13061		10	18		D13049	10	18		YR301-YR328
0007	18	PA			15-5	44-21-47	D13061		11	18		D13049	11	18		YN501
0007	18	PA			16-11	44-21-47	D13061		11	18		D13049	11	18		YR301-YR328
0008	18	PA			15-5	44-21-47	D13061		3	18		D13049	3	18		YN501
0008	18	PA			16-11	44-21-47	D13061		3	18		D13049	3	18		YR301-YR328
0009	18	PA			15-11	44-21-47	D13093		9	18		D13065	9	18		YN501
0009	18	PA			23-2	44-21-47	D13093		9	18		D13065	9	18		YR301-YR328
0010	18	CQ			15-11	44-21-47	D13093		10	18		D13065	10	18		YN501
0010	18	CQ			23-2	44-21-47	D13093		10	18		D13065	10	18		YR301-YR328
0011	18	PA			15-11	44-21-47	D13093		11	18		D13065	11	18		YN501
0011	18	PA			23-2	44-21-47	D13093		11	18		D13065	11	18		YR301-YR328
0012	18	PA			15-11	44-21-47	D13093		3	18		D13065	3	18		YN501
0012	18	PA			23-2	44-21-47	D13093		3	18		D13065	3	18		YR301-YR328
0013	18	PA			16-10	44-21-47	D13109		3	18		D13097	3	18		YN501
0013	18	PA			20-3	44-21-47	D13097		3	18		D13109	3	18		YR301-YR328
0014	18	PA			16-10	44-21-47	D13109		11	18		D13097	11	18		YN501
0014	18	PA			20-3	44-21-47	D13097		11	18		D13109	11	18		YR301-YR328
0015	18	CQ			16-10	44-21-47	D13109		10	18		D13097	10	18		YN501
0015	18	CQ			20-3	44-21-47	D13097		10	18		D13109	10	18		YR301-YR328
0016	18	PA			16-10	44-21-47	D13109		9	18		D13097	9	18		YN501
0016	18	PA			20-3	44-21-47	D13097		9	18		D13109	9	18		YR301-YR328
0017	18	PA			19-2	44-21-47	D13229		3	18		D13113	3	18		YR301-YR328
0018	18	PA			19-2	44-21-47	D13229		11	18		D13113	11	18		YR301-YR328
0019	18	CQ			19-2	44-21-47	D13229		10	18		D13113	10	18		YR301-YR328
0020	18	PA			19-2	44-21-47	D13229		9	18		D13113	9	18		YR301-YR328
0021	18	PA			15-2	44-21-47	GD03808	ST..	1			D13113	3	18		YN501
0021	18	PA			16-5	44-21-47	GD03808	ST..	1			D13233	3	18		YR301-YR328
2501B	20	X2	AA		7-0	44-21-47	D45433P		5			D13045	2			YN501

WIRE LIST

D280A108

91-21-11

Section W3670

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From			To			Effectivity		
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W3671	286A3671			IFE - (BSI) SERVER BASED SYSTEM PSU - OVERHEAD VIDEO RIGHT AFT (continued)										
2501B	20	X2	AA	8-6	44-21-47	D45433P		5		D13045	2		YR301-YR328	
2501R	20	X2	AA	0-0	44-21-47	D45433P		4		D13045	1		YN501-YR328	
2501Z			AA	0-0	44-21-47	D45433P		6		D13045	4		YN501-YR328	
2502B	20	X2	AB	15-5	44-21-47	D13061		2		D13049	2		YN501	
2502B	20	X2	AB	16-11	44-21-47	D13061		2		D13049	2		YR301-YR328	
2502R	20	X2	AB	0-0	44-21-47	D13061		1		D13049	1		YN501-YR328	
2502Z			AB	0-0	44-21-47	D13061		4		D13049	4		YN501-YR328	
2503B	20	X2	AC	15-11	44-21-47	D13093		2		D13065	2		YN501	
2503B	20	X2	AC	23-2	44-21-47	D13093		2		D13065	2		YR301-YR328	
2503R	20	X2	AC	0-0	44-21-47	D13093		1		D13065	1		YN501-YR328	
2503Z			AC	0-0	44-21-47	D13093		4		D13065	4		YN501-YR328	
2504B	20	X2	AD	16-10	44-21-47	D13109		2		D13097	2		YN501	
2504B	20	X2	AD	20-3	44-21-47	D13097		2		D13109	2		YR301-YR328	
2504R	20	X2	AD	0-0	44-21-47	D13109		1		D13097	1		YN501	
2504R	20	X2	AD	0-0	44-21-47	D13097		1		D13109	1		YR301-YR328	
2504Z			AD	0-0	44-21-47	D13109		4		D13097	4		YN501	
2504Z			AD	0-0	44-21-47	D13097		4		D13109	4		YR301-YR328	
2505B	20	X2	AE	19-2	44-21-47	D13229		2		D13113	2		YR301-YR328	
2505R	20	X2	AE	0-0	44-21-47	D13229		1		D13113	1		YR301-YR328	
2505Z			AE	0-0	44-21-47	D13229		4		D13113	4		YR301-YR328	
4001B	24	FS	KA	23-6	44-21-47	D13019	A-3			D13047	A-4		YN501	
4001B	24	FS	KA	25-2	44-21-47	D13035	A-3			D13047	A-4		YR301-YR328	
4001G	24	FS	KA	0-0	44-21-47	D13019	A-4			D13047	A-3		YN501	
4001G	24	FS	KA	0-0	44-21-47	D13035	A-4			D13047	A-3		YR301-YR328	
4001R	24	FS	KA	0-0	44-21-47	D13019	A-1			D13047	A-2		YN501	
4001R	24	FS	KA	0-0	44-21-47	D13035	A-1			D13047	A-2		YR301-YR328	
4001Y	24	FS	KA	0-0	44-21-47	D13019	A-2			D13047	A-1		YN501	
4001Y	24	FS	KA	0-0	44-21-47	D13035	A-2			D13047	A-1		YR301-YR328	
4001Z			KA	0-0	44-21-47	D13019	=CA			D13047	=CA		YN501	
4001Z			KA	0-0	44-21-47	D13035	=CA			D13047	=CA		YR301-YR328	
4003B	24	FS	KC	15-5	44-21-47	D13063	A-4			D13051	A-3		YN501	
4003B	24	FS	KC	16-11	44-21-47	D13063	A-4			D13051	A-3		YR301-YR328	
4003G	24	FS	KC	0-0	44-21-47	D13063	A-3			D13051	A-4		YN501-YR328	
4003R	24	FS	KC	0-0	44-21-47	D13063	A-2			D13051	A-1		YN501-YR328	
4003Y	24	FS	KC	0-0	44-21-47	D13063	A-1			D13051	A-2		YN501-YR328	
4003Z			KC	0-0	44-21-47	D13063	=CA			D13051	=CA		YN501-YR328	
4004B	24	FS	KD	15-11	44-21-47	D13095	A-4			D13067	A-3		YN501	
4004B	24	FS	KD	23-2	44-21-47	D13095	A-4			D13067	A-3		YR301-YR328	
4004G	24	FS	KD	0-0	44-21-47	D13095	A-3			D13067	A-4		YN501-YR328	

WIRE LIST

D280A108

91-21-11

Section W3670

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W3671	286A3671				IFE - (BSI) SERVER BASED SYSTEM PSU - OVERHEAD VIDEO RIGHT AFT (continued)											
4004R	24		FS	KD	0-0	44-21-47	D13095		A-2			D13067	A-1			YN501-YR328
4004Y	24		FS	KD	0-0	44-21-47	D13095		A-1			D13067	A-2			YN501-YR328
4004Z				KD	0-0	44-21-47	D13095		=CA			D13067	=CA			YN501-YR328
4005B	24		FS	KE	16-10	44-21-47	D13111		A-4			D13099	A-3			YN501
4005B	24		FS	KE	20-3	44-21-47	D13111		A-4			D13099	A-3			YR301-YR328
4005G	24		FS	KE	0-0	44-21-47	D13111		A-3			D13099	A-4			YN501-YR328
4005R	24		FS	KE	0-0	44-21-47	D13111		A-2			D13099	A-1			YN501-YR328
4005Y	24		FS	KE	0-0	44-21-47	D13111		A-1			D13099	A-2			YN501-YR328
4005Z				KE	0-0	44-21-47	D13111		=CA			D13099	=CA			YN501-YR328
4006B	24		FS	KF	19-2	44-21-47	D13231		A-4			D13115	A-3			YR301-YR328
4006G	24		FS	KF	0-0	44-21-47	D13231		A-3			D13115	A-4			YR301-YR328
4006R	24		FS	KF	0-0	44-21-47	D13231		A-2			D13115	A-1			YR301-YR328
4006Y	24		FS	KF	0-0	44-21-47	D13231		A-1			D13115	A-2			YR301-YR328
4006Z				KF	0-0	44-21-47	D13231		=CA			D13115	=CA			YR301-YR328
4007B	24		FS	KG	13-2	44-21-47	D45451J		2			D13115	A-3			YN501
4007B	24		FS	KG	14-8	44-21-47	D45451J		2			D13235	A-3			YR301-YR328
4007G	24		FS	KG	0-0	44-21-47	D45451J		4			D13115	A-4			YN501
4007G	24		FS	KG	0-0	44-21-47	D45451J		4			D13235	A-4			YR301-YR328
4007R	24		FS	KG	0-0	44-21-47	D45451J		1			D13115	A-1			YN501
4007R	24		FS	KG	0-0	44-21-47	D45451J		1			D13235	A-1			YR301-YR328
4007Y	24		FS	KG	0-0	44-21-47	D45451J		3			D13115	A-2			YN501
4007Y	24		FS	KG	0-0	44-21-47	D45451J		3			D13235	A-2			YR301-YR328
4007Z				KG	0-0	44-21-47	D45451J		PERB			D13115	=CA			YN501
4007Z				KG	0-0	44-21-47	D45451J		PERB			D13235	=CA			YR301-YR328

WIRE LIST

D280A108

91-21-11
Section W3670
Page 3 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To			Effectivity					
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type		Splice	Equip	Term	Type	Splice
I	W3695	286A3695			IFE -(BSI) BRKT AB0373 JUMPER BUNDLE FOR HDD-OML											
I	4001B	24		FS	KA	2-3	44-21-12	D12889P		A-3		D12883P		A-4		YR303-YR328
I	4001G	24		FS	KA	0-0	44-21-12	D12889P		A-4		D12883P		A-3		YR303-YR328
I	4001R	24		FS	KA	0-0	44-21-12	D12889P		A-1		D12883P		A-2		YR303-YR328
I	4001Y	24		FS	KA	0-0	44-21-12	D12889P		A-2		D12883P		A-1		YR303-YR328
I	4001Z				KA	0-0	44-21-12	D12889P		= CA		D12883P		= CA		YR303-YR328
I	4002B	24		FS	KB	2-3	44-21-12	D12889P		B-3		D12883P		B-4		YR303-YR328
I	4002G	24		FS	KB	0-0	44-21-12	D12889P		B-4		D12883P		B-3		YR303-YR328
I	4002R	24		FS	KB	0-0	44-21-12	D12889P		B-1		D12883P		B-2		YR303-YR328
I	4002Y	24		FS	KB	0-0	44-21-12	D12889P		B-2		D12883P		B-1		YR303-YR328
I	4002Z				KB	0-0	44-21-12	D12889P		= CB		D12883P		= CB		YR303-YR328

WIRE LIST

D280A108

91-21-11

Section W3690

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3701	286A3701				VIU/CIU BRACKET STA 344 TO CAMERA 1 BRACKET STA 2XX											
0001	20		PA		2-6	23-70-11		D37001J		7		GD11100	ST..	1		YL951-YR328
2501B	20		X2	AA	9-11	23-70-11		D37001J		2		D40351J		2		YL951-YR328
2501R	20		X2	AA	0-0	23-70-11		D37001J		1		D40351J		1		YL951-YR328
2501Z				AA	0-0	23-70-11		D37001J		S/R		D40351J		S/R		YL951-YR328
2502B	24		OT	AB	9-11	23-70-11		D37001J		4		D40351J		4		YL951-YR328
2502W	24		OT	AB	0-0	23-70-11		D37001J		3		D40351J		3		YL951-YR328
2502Z				AB	0-0	23-70-11		D37001J		S/R		D40351J		S/R		YL951-YR328
2503B	22		X2	AC	9-11	23-70-11		D37001J		6		D40351J		6		YL951-YR328
2503R	22		X2	AC	0-0	23-70-11		D37001J		5		D40351J		5		YL951-YR328
2503Z				AC	0-0	23-70-11		D37001J		S/R		D40351J		S/R		YL951-YR328
W3702	286A3702				VIU/CIU BRACKET STA 344 TO CAMERA 2 BRACKET STA 2XX											
0001	20		PA		3-8	23-70-11		D37002J		7		GD03734	ST..	1A		YL951-YR328
2501B	20		X2	AA	1-6	23-70-11		D37002J		2		D40353J		2		YL951-YR328
2501R	20		X2	AA	0-0	23-70-11		D37002J		1		D40353J		1		YL951-YR328
2501Z				AA	0-0	23-70-11		D37002J		S/R		D40353J		S/R		YL951-YR328
2502B	24		OT	AB	1-6	23-70-11		D37002J		4		D40353J		4		YL951-YR328
2502W	24		OT	AB	0-0	23-70-11		D37002J		3		D40353J		3		YL951-YR328
2502Z				AB	0-0	23-70-11		D37002J		S/R		D40353J		S/R		YL951-YR328
2503B	22		X2	AC	1-6	23-70-11		D37002J		6		D40353J		6		YL951-YR328
2503R	22		X2	AC	0-0	23-70-11		D37002J		5		D40353J		5		YL951-YR328
2503Z				AC	0-0	23-70-11		D37002J		S/R		D40353J		S/R		YL951-YR328
W3703	286A3703				VIU/CIU BRACKET STA 344 TO CAMERA 3 BRACKET STA 2XX											
0001	20		PA		2-9	23-70-11		D37003J		7		GD03924	ST..	1		YL951-YR328
2501B	20		X2	AA	11-0	23-70-11		D37003J		2		D40355J		2		YL951-YR328
2501R	20		X2	AA	0-0	23-70-11		D37003J		1		D40355J		1		YL951-YR328
2501Z				AA	0-0	23-70-11		D37003J		S/R		D40355J		S/R		YL951-YR328
2502B	24		OT	AB	11-0	23-70-11		D37003J		4		D40355J		4		YL951-YR328
2502W	24		OT	AB	0-0	23-70-11		D37003J		3		D40355J		3		YL951-YR328
2502Z				AB	0-0	23-70-11		D37003J		S/R		D40355J		S/R		YL951-YR328
2503B	22		X2	AC	11-0	23-70-11		D37003J		6		D40355J		6		YL951-YR328
2503R	22		X2	AC	0-0	23-70-11		D37003J		5		D40355J		5		YL951-YR328
2503Z				AC	0-0	23-70-11		D37003J		S/R		D40355J		S/R		YL951-YR328
W3704	286A3704				TRANSFORMER BKT STA 340 TO QUICK DISC. STA 235 (CAPT. VIDEO DISPLAY)											
001CO				BA	0-0	31-62-42		D12241		= C1		D10030J		= C1		YL951, YN231

WIRE LIST

D280A108

91-21-11

Section W3700

Page 1

Nov 12/2012

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3704	286A3704	TRANSFORMER BKT STA 340 TO QUICK DISC. STA 235 (CAPT. VIDEO DISPLAY) (continued)													
001CO				BA	0-0	31-62-42	D12241	=	C1		D10030P	=	C1		YL952-YL999, YN232-YN260
I 001CO				BA	0-0	31-62-42	D14818	=	C1		D10030P	=	C1		YN501-YR328
001CX		0F		BA	27-11	31-62-42	D12241	=	A1		D10030J	=	A1		YL951, YN231
001CX		0F		BA	33-9	31-62-42	D12241	=	A1		D10030P	=	A1		YL952-YL999, YN232-YN260
I 001CX		0F		BA	36-6	31-62-42	D14818	=	A1		D10030P	=	A1		YN501-YR328
W3705	286A3705	TRANSFORMER BKT STA 340 TO QUICK DISC. STA 235 (CTR. VIDEO DISPLAY)													
001CO				BA	0-0	31-62-42	D12245	=	C1		D10034J	=	C1		YL951, YN231
001CO				BA	0-0	31-62-42	D12245	=	C1		D10034P	=	C1		YL952-YL999, YN232-YN260
I 001CO				BA	0-0	31-62-42	D14820	=	C1		D10034P	=	C1		YN501-YR328
001CX		0F		BA	28-1	31-62-42	D12245	=	A1		D10034J	=	A1		YL951, YN231
001CX		0F		BA	33-11	31-62-42	D12245	=	A1		D10034P	=	A1		YL952-YL999, YN232-YN260
I 001CX		0F		BA	36-7	31-62-42	D14820	=	A1		D10034P	=	A1		YN501-YR328
W3706	286A3706	TRANSFORMER BKT STA 340 TO QUICK DISC. STA 235 (F/O VIDEO DISPLAY)													
001CO				BA	0-0	31-62-42	D12249	=	C1		D10032J	=	C1		YL951, YN231
001CO				BA	0-0	31-62-42	D12249	=	C1		D10032P	=	C1		YL952-YL999, YN232-YN260
I 001CO				BA	0-0	31-62-42	D14822	=	C1		D10032P	=	C1		YN501-YR328
001CX		0F		BA	28-4	31-62-42	D12249	=	A1		D10032J	=	A1		YL951, YN231
001CX		0F		BA	34-3	31-62-42	D12249	=	A1		D10032P	=	A1		YL952-YL999, YN232-YN260
I 001CX		0F		BA	36-11	31-62-42	D14822	=	A1		D10032P	=	A1		YN501-YR328
W3707	286A3707	VIU/CIU BRACKET STA 344 TO CAPT EFB STA 205													
2501B	24	ON		AA	28-10	23-70-11	D00796	CAP	Y		D40361J		2		YN231-YN260
2501W	24	ON		AA	0-0	23-70-11	D00796	CAP	Y		D40361J		1		YN231-YN260
2501Z				AA	0-0	23-70-11	D00796	DED			D40361J	PERB			YN231-YN260
2502B	24	ON		AB	28-10	23-70-11	D00796	CAP	Y		D40361J		4		YN231-YN260
2502W	24	ON		AB	0-0	23-70-11	D00796	CAP	Y		D40361J		3		YN231-YN260
2502Z				AB	0-0	23-70-11	D00796	DED			D40361J	PERB			YN231-YN260
W3708	286A3708	VIU/CIU BRACKET STA 344 TO F/O EFB STA 205													
2501B	24	ON		AA	28-7	23-70-11	D00798	CAP	Y		D40359J		2		YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W3700

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3708	286A3708			VIU/CIU BRACKET STA 344 TO F/O EFB STA 205 (continued)											
2501W	24	ON		AA	0-0	23-70-11	D00798	CAP	Y		D40359J	1			YN231-YN260
2501Z				AA	0-0	23-70-11	D00798	DED			D40359J	PERB			YN231-YN260
2502B	24	ON		AB	28-7	23-70-11	D00798	CAP	Y		D40359J	4			YN231-YN260
2502W	24	ON		AB	0-0	23-70-11	D00798	CAP	Y		D40359J	3			YN231-YN260
2502Z				AB	0-0	23-70-11	D00798	DED			D40359J	PERB			YN231-YN260
W3709	286A3709			VIU/CIU BRACKET STA 344 TO THE CAMERA CONTROL PANEL IN THE P8 PANEL											
0001	20	PA			4-3	33-11-41	D12237		1		TB0801W	B013	1A		YL951-YL968, YN231-YN236, YN501-YR314
0001	20	PA			4-3	33-11-41	D12237		1		TB0801W	B013	1		YL969-YL999, YN237-YN260, YR315-YR328
0002	20	PA			4-1	33-11-41	D12237		2		GD00807	AC..	1A		YL951-YR328
0003	24	PK			30-11	31-62-42	SP00465		9		D40357J	7			YL951-YR328
2501B	24	Y2	AA		32-6	23-70-11	D12237		8		D40357J	6			YL951-YR328
2501R	24	Y2	AA		0-0	23-70-11	D12237		7		D40357J	5			YL951-YR328
2501Z			AA		0-0	23-70-11	D12237		S/R		D40357J	S/R			YL951-YR328
4501B	24	Y4	LA		32-6	23-70-11	D12237		6		D40357J	4			YL951-YR328
4501G	24	Y4	LA		0-0	23-70-11	D12237		5		D40357J	3			YL951-YR328
4501R	24	Y4	LA		0-0	23-70-11	D12237		3		D40357J	1			YL951-YR328
4501Y	24	Y4	LA		0-0	23-70-11	D12237		4		D40357J	2			YL951-YR328
4501Z			LA		0-0	23-70-11	D12237		S/R		D40357J	S/R			YL951-YR328

WIRE LIST

D280A108

91-21-11
Section W3700
Page 3 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

	Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I	W3710	286A3710			VIU/CIU BRACKET STA 344 TO THE TRANSFORMER'S BRACKETS STA 340											
	2501B	24		OT	AA	7-1	23-70-11	D12239			4	D40365J			2	YL951-YN260
I	2501B	24		OT	AA	12-5	23-70-11	D12877			4	D40365J			2	YN501-YR328
	2501W	24		OT	AA	0-0	23-70-11	D12239			3	D40365J			1	YL951-YN260
I	2501W	24		OT	AA	0-0	23-70-11	D12877			3	D40365J			1	YN501-YR328
	2501Z				AA	0-0	23-70-11	D12239		S/R		D40365J		S/R		YL951-YN260
I	2501Z				AA	0-0	23-70-11	D12877		S/R		D40365J		S/R		YN501-YR328
	2502B	24		OT	AB	9-2	23-70-11	D12243			4	D40365J			4	YL951-YN260
I	2502B	24		OT	AB	12-8	23-70-11	D12879			4	D40365J			4	YN501-YR328
	2502W	24		OT	AB	0-0	23-70-11	D12243			3	D40365J			3	YL951-YN260
I	2502W	24		OT	AB	0-0	23-70-11	D12879			3	D40365J			3	YN501-YR328
	2502Z				AB	0-0	23-70-11	D12243		S/R		D40365J		S/R		YL951-YN260
I	2502Z				AB	0-0	23-70-11	D12879		S/R		D40365J		S/R		YN501-YR328
	2503B	24		OT	AC	9-4	23-70-11	D12247			4	D40365J			6	YL951-YN260
I	2503B	24		OT	AC	12-11	23-70-11	D12881			4	D40365J			6	YN501-YR328
	2503W	24		OT	AC	0-0	23-70-11	D12247			3	D40365J			5	YL951-YN260
I	2503W	24		OT	AC	0-0	23-70-11	D12881			3	D40365J			5	YN501-YR328
	2503Z				AC	0-0	23-70-11	D12247		S/R		D40365J		S/R		YL951-YN260
I	2503Z				AC	0-0	23-70-11	D12881		S/R		D40365J		S/R		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W3710

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3801	286A3801					CAMERA 1 BRACKET STA 288 TO CAMERA 1 STA 285									
0001	20		PA		4-2	23-70-11	D37001P	7			D12325	G			YL951-YR328
2501B	20		X2	AA	4-2	23-70-11	D37001P	2			D12325	E			YL951-YR328
2501R	20		X2	AA	0-0	23-70-11	D37001P	1			D12325	D			YL951-YR328
2501Z				AA	0-0	23-70-11	D37001P	S/R			D12325	S/R			YL951-YR328
2502B	24		OT	AB	4-2	23-70-11	D37001P	4			D12325	B			YL951-YR328
2502W	24		OT	AB	0-0	23-70-11	D37001P	3			D12325	A			YL951-YR328
2502Z				AB	0-0	23-70-11	D37001P	S/R			D12325	S/R			YL951-YR328
W3802	286A3802					VIU/CIU BRACKET STA 358 TO CAMERA 2 STA 340									
0001	20		PA		7-7	23-70-11	D37002P	7			D12327	G			YL951-YN260
0001	20		PA		10-7	23-70-11	D37002P	7			D11423	G			YN501-YR328
0002	24		PK		0-7	23-70-11	D12327	H			D12327	K			YL951-YN260
0002	24		PK		0-7	23-70-11	D11423	H			D11423	K			YN501-YR328
2501B	20		X2	AA	7-7	23-70-11	D37002P	2			D12327	E			YL951-YN260
2501B	20		X2	AA	10-7	23-70-11	D37002P	2			D11423	E			YN501-YR328
2501R	20		X2	AA	0-0	23-70-11	D37002P	1			D12327	D			YL951-YN260
2501R	20		X2	AA	0-0	23-70-11	D37002P	1			D11423	D			YN501-YR328
2501Z				AA	0-0	23-70-11	D37002P	S/R			D12327	S/R			YL951-YN260
2501Z				AA	0-0	23-70-11	D37002P	S/R			D11423	S/R			YN501-YR328
2502B	24		OT	AB	7-7	23-70-11	D37002P	4			D12327	B			YL951-YN260
2502B	24		OT	AB	10-7	23-70-11	D37002P	4			D11423	B			YN501-YR328
2502W	24		OT	AB	0-0	23-70-11	D37002P	3			D12327	A			YL951-YN260
2502W	24		OT	AB	0-0	23-70-11	D37002P	3			D11423	A			YN501-YR328
2502Z				AB	0-0	23-70-11	D37002P	S/R			D12327	S/R			YL951-YN260
2502Z				AB	0-0	23-70-11	D37002P	S/R			D11423	S/R			YN501-YR328
W3803	286A3803					CAMERA 3 BRACKET STA 352 TO CAMERA 3 STA 333									
0001	20		PA		6-2	23-70-11	D37003P	7			D12329	G			YL951-YR328
0002	24		PK		0-7	23-70-11	D12329	H			D12329	K			YL951-YR328
2501B	20		X2	AA	6-2	23-70-11	D37003P	2			D12329	E			YL951-YR328
2501R	20		X2	AA	0-0	23-70-11	D37003P	1			D12329	D			YL951-YR328
2501Z				AA	0-0	23-70-11	D37003P	S/R			D12329	S/R			YL951-YR328
2502B	24		OT	AB	6-2	23-70-11	D37003P	4			D12329	B			YL951-YR328
2502W	24		OT	AB	0-0	23-70-11	D37003P	3			D12329	A			YL951-YR328
2502Z				AB	0-0	23-70-11	D37003P	S/R			D12329	S/R			YL951-YR328
W3805	286A3805					VIU/CIU BRACKET STA 358 TO VIDEO CONTROL UNIT STA 344									
0001	20		PA		2-7	23-70-11	D40349P	3			D12323	C			YL951-YN260

WIRE LIST

D280A108

91-21-11

Section W3800

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3805		286A3805			VIU/CIU BRACKET STA 358 TO VIDEO CONTROL UNIT STA 344 (continued)											
0001		20		PA		9-6	23-70-11	D40349P				D12865		C		YN501-YR328
0002		24		PK		2-1	23-70-11	D12321		A-		GD11108		ST..	1	YL951-YN260
0002		24		PK		8-7	23-70-11	D12863		A-		GD11108		ST..	1	YN501-YR328
0003		24		PK		2-4	23-70-11	D40357P			7	D12321		T-		YL951-YN260
0003		24		PK		9-6	23-70-11	D40357P			7	D12863		T-		YN501-YR328
0004		24		PK		2-1	23-70-11	D12321		JJ		GD11108		ST..	1	YL951-YN260
0004		24		PK		8-7	23-70-11	D12863		JJ		GD11108		ST..	1	YN501-YR328
2001B		20		PB	EA	2-7	23-70-11	D40349P			2	D12323		F		YL951-YN260
2001B		20		PB	EA	9-6	23-70-11	D40349P			2	D12865		F		YN501-YR328
2001R		20		PB	EA	0-0	23-70-11	D40349P			1	D12323		A		YL951-YN260
2001R		20		PB	EA	0-0	23-70-11	D40349P			1	D12865		A		YN501-YR328
2501B		20		X2	AA	2-6	23-70-11	D40351P			2	D12317		B		YL951-YN260
2501B		20		X2	AA	10-0	23-70-11	D40351P			2	D12859		B		YN501-YR328
2501R		20		X2	AA	0-0	23-70-11	D40351P			1	D12317		C		YL951-YN260
2501R		20		X2	AA	0-0	23-70-11	D40351P			1	D12859		C		YN501-YR328
2501Z					AA	0-0	23-70-11	D40351P		S/R		D12317		PERB		YL951-YN260
2501Z					AA	0-0	23-70-11	D40351P		S/R		D12859		PERB		YN501-YR328
2502B		24		OT	AB	2-6	23-70-11	D40351P			4	D12317		C-		YL951-YN260
2502B		24		OT	AB	10-0	23-70-11	D40351P			4	D12859		C-		YN501-YR328
2502W		24		OT	AB	0-0	23-70-11	D40351P			3	D12317		A		YL951-YN260
2502W		24		OT	AB	0-0	23-70-11	D40351P			3	D12859		A		YN501-YR328
2502Z					AB	0-0	23-70-11	D40351P		S/R		D12317		PERB		YL951-YN260
2502Z					AB	0-0	23-70-11	D40351P		S/R		D12859		PERB		YN501-YR328
2503B		20		X2	AC	2-7	23-70-11	D40355P			2	D12317		K		YL951-YN260
2503B		20		X2	AC	10-0	23-70-11	D40355P			2	D12859		K		YN501-YR328
2503R		20		X2	AC	0-0	23-70-11	D40355P			1	D12317		L		YL951-YN260
2503R		20		X2	AC	0-0	23-70-11	D40355P			1	D12859		L		YN501-YR328
2503Z					AC	0-0	23-70-11	D40355P		S/R		D12317		PERB		YL951-YN260
2503Z					AC	0-0	23-70-11	D40355P		S/R		D12859		PERB		YN501-YR328
2504B		24		OT	AD	2-7	23-70-11	D40355P			4	D12317		H		YL951-YN260
2504B		24		OT	AD	10-0	23-70-11	D40355P			4	D12859		H		YN501-YR328
2504W		24		OT	AD	0-0	23-70-11	D40355P			3	D12317		J		YL951-YN260
2504W		24		OT	AD	0-0	23-70-11	D40355P			3	D12859		J		YN501-YR328
2504Z					AD	0-0	23-70-11	D40355P		S/R		D12317		PERB		YL951-YN260
2504Z					AD	0-0	23-70-11	D40355P		S/R		D12859		PERB		YN501-YR328
2505B		24		Y2	AE	2-4	23-70-11	D40357P			6	D12321		GG		YL951-YN260
2505B		24		Y2	AE	9-6	23-70-11	D40357P			6	D12863		GG		YN501-YR328
2505R		24		Y2	AE	0-0	23-70-11	D40357P			5	D12321		M		YL951-YN260
2505R		24		Y2	AE	0-0	23-70-11	D40357P			5	D12863		M		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W3800

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3805	286A3805				VIU/CIU BRACKET STA 358 TO VIDEO CONTROL UNIT STA 344 (continued)											
2505Z				AE	0-0	23-70-11		D40357P		S/R		D12321		PERB		YL951-YN260
2505Z				AE	0-0	23-70-11		D40357P		S/R		D12863		PERB		YN501-YR328
2506B	20	X2		AF	2-7	23-70-11		D40353P		2		D12317		F		YL951-YN260
2506B	20	X2		AF	10-0	23-70-11		D40353P		2		D12859		F		YN501-YR328
2506R	20	X2		AF	0-0	23-70-11		D40353P		1		D12317		G		YL951-YN260
2506R	20	X2		AF	0-0	23-70-11		D40353P		1		D12859		G		YN501-YR328
2506Z				AF	0-0	23-70-11		D40353P		S/R		D12317		PERB		YL951-YN260
2506Z				AF	0-0	23-70-11		D40353P		S/R		D12859		PERB		YN501-YR328
2507B	24	OT		AG	2-7	23-70-11		D40353P		4		D12317		D		YL951-YN260
2507B	24	OT		AG	10-0	23-70-11		D40353P		4		D12859		D		YN501-YR328
2507W	24	OT		AG	0-0	23-70-11		D40353P		3		D12317		E		YL951-YN260
2507W	24	OT		AG	0-0	23-70-11		D40353P		3		D12859		E		YN501-YR328
2507Z				AG	0-0	23-70-11		D40353P		S/R		D12317		PERB		YL951-YN260
2507Z				AG	0-0	23-70-11		D40353P		S/R		D12859		PERB		YN501-YR328
2508B	24	OT		AH	2-4	23-70-11		D40365P		2		D12319		C-		YL951-YN260
2508B	24	OT		AH	9-8	23-70-11		D40365P		2		D12861		C-		YN501-YR328
2508W	24	OT		AH	0-0	23-70-11		D40365P		1		D12319		A		YL951-YN260
2508W	24	OT		AH	0-0	23-70-11		D40365P		1		D12861		A		YN501-YR328
2508Z				AH	0-0	23-70-11		D40365P		S/R		D12319		PERB		YL951-YN260
2508Z				AH	0-0	23-70-11		D40365P		S/R		D12861		PERB		YN501-YR328
2509B	24	OT		AI	2-4	23-70-11		D40365P		4		D12319		E		YL951-YN260
2509B	24	OT		AI	9-8	23-70-11		D40365P		4		D12861		E		YN501-YR328
2509W	24	OT		AI	0-0	23-70-11		D40365P		3		D12319		D		YL951-YN260
2509W	24	OT		AI	0-0	23-70-11		D40365P		3		D12861		D		YN501-YR328
2509Z				AI	0-0	23-70-11		D40365P		S/R		D12319		PERB		YL951-YN260
2509Z				AI	0-0	23-70-11		D40365P		S/R		D12861		PERB		YN501-YR328
2510B	24	OT		AJ	2-4	23-70-11		D40365P		6		D12319		EE		YL951-YN260
2510B	24	OT		AJ	9-8	23-70-11		D40365P		6		D12861		EE		YN501-YR328
2510W	24	OT		AJ	0-0	23-70-11		D40365P		5		D12319		DD		YL951-YN260
2510W	24	OT		AJ	0-0	23-70-11		D40365P		5		D12861		DD		YN501-YR328
2510Z				AJ	0-0	23-70-11		D40365P		S/R		D12319		PERB		YL951-YN260
2510Z				AJ	0-0	23-70-11		D40365P		S/R		D12861		PERB		YN501-YR328
4501B	24	Y4		LA	2-4	23-70-11		D40357P		4		D12321		R		YL951-YN260
4501B	24	Y4		LA	9-6	23-70-11		D40357P		4		D12863		R		YN501-YR328
4501G	24	Y4		LA	0-0	23-70-11		D40357P		3		D12321		U		YL951-YN260
4501G	24	Y4		LA	0-0	23-70-11		D40357P		3		D12863		U		YN501-YR328
4501R	24	Y4		LA	0-0	23-70-11		D40357P		1		D12321		HH		YL951-YN260
4501R	24	Y4		LA	0-0	23-70-11		D40357P		1		D12863		HH		YN501-YR328
4501Y	24	Y4		LA	0-0	23-70-11		D40357P		2		D12321		X		YL951-YN260

WIRE LIST

D280A108

91-21-11

Section W3800

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W3805	286A3805			VIU/CIU BRACKET STA 358 TO VIDEO CONTROL UNIT STA 344 (continued)											
4501Y	24		Y4	LA	0-0	23-70-11	D40357P		2		D12863		X		YN501-YR328
4501Z				LA	0-0	23-70-11	D40357P		S/R		D12321		PERB		YL951-YN260
4501Z				LA	0-0	23-70-11	D40357P		S/R		D12863		PERB		YN501-YR328

For training purposes only!

WIRE LIST

D280A108

91-21-11

Section W3800

Page 4 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I W3895	286A3895			ATC TOP ANT E1 RACK (S942) TO STA 430.25 (M1406)											
I 001CO				AA	0-0	34-53-31	D02529		= C1		D02703		= C1		ALL
I 001CX		0H		AA	30-0	34-53-31	D02529		= A1		D02703		= A1		ALL

For training purposes only!

WIRE LIST

D280A108

91-21-11

Section W3890

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From					To						
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I	W3901	286A3901			COAX ASSY - ELT ANTENNA											
I	001CO			AA	0-0	23-24-11	D02905	= C1			D02907	= C1			YL951-YR328	
I	001CX			0F	AA	6-10	23-24-11	D02905	= A1			D02907	= A1		YL951-YR328	

For training purposes only!

WIRE LIST

D280A108

91-21-11

Section W3900

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I W4001	286A4001			TCAS TOP ANTENNA (E1-1 SHELF)											
I 001CO				AA	0-0	34-45-21	D04609P		= C1		D04625P		= C1		ALL
I 001CX		0G		AA	24-0	34-45-21	D04609P		= A1		D04625P		= A1		ALL
I 002CO				AB	0-0	34-45-21	D04611P		= C1		D04627P		= C1		ALL
I 002CX		0G		AB	24-0	34-45-21	D04611P		= A1		D04627P		= A1		ALL
I 003CO				AC	0-0	34-45-21	D04613P		= C1		D04629P		= C1		ALL
I 003CX		0G		AC	24-0	34-45-21	D04613P		= A1		D04629P		= A1		ALL
I 004CO				AD	0-0	34-45-21	D04615P		= C1		D04633P		= C1		ALL
I 004CX		0G		AD	24-0	34-45-21	D04615P		= A1		D04633P		= A1		ALL
I W4009	286A4009			TCAS TOP ANTENNA											
I 001CO				AA	0-0	34-45-21	D04625J		= C1		D02745		= C1		ALL
I 001CX		0H		AA	3-0	34-45-21	D04625J		= A1		D02745		= A1		ALL
I 002CO				AB	0-0	34-45-21	D04627J		= C1		D02747		= C1		ALL
I 002CX		0H		AB	3-0	34-45-21	D04627J		= A1		D02747		= A1		ALL
I 003CO				AC	0-0	34-45-21	D04629J		= C1		D02749		= C1		ALL
I 003CX		0H		AC	3-0	34-45-21	D04629J		= A1		D02749		= A1		ALL
I 004CO				AD	0-0	34-45-21	D04633J		= C1		D02751		= C1		ALL
I 004CX		0H		AD	3-0	34-45-21	D04633J		= A1		D02751		= A1		ALL

WIRE LIST

D280A108

91-21-11
Section W4000
Page 1 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description	Diagram	From			To			Effectivity		
	GA	CO	TY				Equip	Term	Type	Splice	Equip	Term		Type	Splice
W4110															
286A4110															
PASS CAB TEMP SENSOR(M2814) TO STA 413 (CEILING) NB2 (BSI)															
5501	22		PA		2-7	21-61-22	D14732		3			D41431J	1		YN501
5502	22		PA		2-7	21-61-22	D14732		1			D41431J	2		YN501
5503	22		PA		2-4	21-61-22	D14736		1			D41431J	3		YN501
5504	20		PA		2-4	21-61-22	D14736		2			D41431J	4		YN501
5505	20		PA		2-4	21-61-22	D14736		3			D41431J	5		YN501
5506	20		PA		2-10	21-61-51	D14734		B			D41431J	6		YN501
5507	20		PA		2-10	21-61-51	D14734		A			D41431J	7		YN501
W4116															
286A4116															
FWD PASS CAB TEMP SENSOR (M2847) TO STA 410 (CEILING)															
0001	24		PK		2-10	21-61-13	D41027J		1			D15020	1		YR301-YR328
0002	20		PA		2-10	21-61-13	D41027J		6			D15020	2		YR301-YR328
0003	20		PA		2-10	21-61-13	D41027J		7			D15020	3		YR301-YR328
0004	20		PA		3-4	21-61-51	D41027J		8			D15018	A		YR301-YR328
0005	20		PA		3-4	21-61-51	D41027J		9			D15018	B		YR301-YR328
2001B	24		PL	GA	3-1	21-61-13	D41027J		2			D15016	1		YR301-YR328
2001R	24		PL	GA	0-0	21-61-13	D41027J		3			D15016	2		YR301-YR328
2002B	24		PL	GB	3-1	21-61-13	D41027J		5			D15016	4		YR301-YR328
2002R	24		PL	GB	0-0	21-61-13	D41027J		4			D15016	3		YR301-YR328
W4118															
286A4118															
AFT PASS CAB TEMP SENSOR (M2848) TO STA 410 (CEILING)															
0001	24		PK		3-10	21-61-14	D41028J		1			D15026	1		YR301-YR328
0002	20		PA		3-10	21-61-14	D41028J		6			D15026	2		YR301-YR328
0003	20		PA		3-10	21-61-14	D41028J		7			D15026	3		YR301-YR328
0004	20		PA		4-3	21-61-51	D41028J		8			D15024	A		YR301-YR328
0005	20		PA		4-3	21-61-51	D41028J		9			D15024	B		YR301-YR328
2001B	24		PL	GA	4-1	21-61-14	D41028J		2			D15022	1		YR301-YR328
2001R	24		PL	GA	0-0	21-61-14	D41028J		3			D15022	2		YR301-YR328
2002B	24		PL	GB	4-1	21-61-14	D41028J		5			D15022	4		YR301-YR328
2002R	24		PL	GB	0-0	21-61-14	D41028J		4			D15022	3		YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4110

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4134	286A4134			AB1050R TO VERTICAL STAB											
1002	20	VF	AB		6-2	27-25-11	D40842J		1		D40268J		10		YC053-YD153
1002	20	VF	AB		6-3	27-25-11	D40842J		1		D40268J		10		YD154-YR328
1002Z			AB		0-0	27-25-11	D40842J		S/R		D40268J		S/R		YC053-YR328
1003	20	VF	AC		6-2	27-25-11	D40842J		2		D40268J		11		YC053-YD153
1003	20	VF	AC		6-3	27-25-11	D40842J		2		D40268J		11		YD154-YR328
1003Z			AC		0-0	27-25-11	D40842J		S/R		D40268J		S/R		YC053-YR328
1004	20	VF	AD		6-2	27-21-11	D40842J		3		D40268J		13		YC053-YD153
1004	20	VF	AD		6-3	27-21-11	D40842J		3		D40268J		13		YD154-YR328
1004Z			AD		0-0	27-21-11	D40842J		S/R		D40268J		S/R		YC053-YR328
1005	20	VF	AE		6-2	27-21-11	D40842J		4		D40268J		12		YC053-YD153
1005	20	VF	AE		6-3	27-21-11	D40842J		4		D40268J		12		YD154-YR328
1005Z			AE		0-0	27-21-11	D40842J		S/R		D40268J		S/R		YC053-YR328
1006	20	VF	AF		6-2	27-21-11	D40842J		5		D40268J		14		YC053-YD153
1006	20	VF	AF		6-3	27-21-11	D40842J		5		D40268J		14		YD154-YR328
1006Z			AF		0-0	27-21-11	D40842J		S/R		D40268J		S/R		YC053-YR328
1007	20	VF	AG		6-2	27-28-11	D40842J		6		D40268J		6		YC053-YD153
1007	20	VF	AG		6-3	27-28-11	D40842J		6		D40268J		6		YD154-YR328
1007Z			AG		0-0	27-28-11	D40842J		S/R		D40268J		S/R		YC053-YR328
1008	20	VF	AH		6-2	27-28-11	D40842J		7		D40268J		7		YC053-YD153
1008	20	VF	AH		6-3	27-28-11	D40842J		7		D40268J		7		YD154-YR328
1008Z			AH		0-0	27-28-11	D40842J		S/R		D40268J		S/R		YC053-YR328
1009	20	VF	AJ		9-10	27-31-37	D40842J		8		D00756		3		YC053-YD153
1009	20	VF	AJ		10-0	27-31-37	D40842J		8		D00756		3		YD154-YD155
1009	20	VF	AJ		9-11	27-31-37	D40842J		8		D00756		3		YD157-YR328
1009Z			AJ		0-0	27-31-37	D40842J		S/R		D00756		DED		YC053-YR328
1010	20	VF	AK		9-10	27-31-37	D40842J		9		D00756		1		YC053-YD153
1010	20	VF	AK		10-0	27-31-37	D40842J		9		D00756		1		YD154-YD155
1010	20	VF	AK		9-11	27-31-37	D40842J		9		D00756		1		YD157-YR328
1010Z			AK		0-0	27-31-37	D40842J		S/R		D00756		DED		YC053-YR328
1011	20	VF	AL		9-10	27-31-37	D40842J		10		D00756		2		YC053-YD153
1011	20	VF	AL		10-0	27-31-37	D40842J		10		D00756		2		YD154-YD155
1011	20	VF	AL		9-11	27-31-37	D40842J		10		D00756		2		YD157-YR328
1011Z			AL		0-0	27-31-37	D40842J		S/R		D00756		DED		YC053-YR328
1012	20	VF	AM		9-10	27-31-37	D40842J		11		D00756		4		YC053-YD153
1012	20	VF	AM		10-0	27-31-37	D40842J		11		D00756		4		YD154-YD155
1012	20	VF	AM		9-11	27-31-37	D40842J		11		D00756		4		YD157-YR328
1012Z			AM		0-0	27-31-37	D40842J		S/R		D00756		DED		YC053-YR328
1013	20	VF	AN		10-6	31-53-11	D40842J		12		SP00054		9		YC053-YR328
1013Z			AN		0-0	31-53-11	D40842J		S/R		GD00078		ST..	1	YC053-YD153

WIRE LIST

D280A108

91-21-11

Section W4130

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice
W4134	286A4134				AB1050R TO VERTICAL STAB (continued)										
1013Z				AN	0-0	31-53-11	D40842J	S/R			GD00024	ST..	1		YD154-YR328
1014	20	VF		AO	10-6	31-53-11	D40842J	13			SP00056		9		YC053-YR328
1014Z				AO	0-0	31-53-11	D40842J	S/R			GD00078	ST..	1		YC053-YD153
1014Z				AO	0-0	31-53-11	D40842J	S/R			GD00024	ST..	1		YD154-YR328
1101	20	GE		BN	7-0	27-25-11	D40842J	21			D40268J		18		YC053-YD155
1101	20	VF		BN	6-3	27-23-11	D40842J	21			D40268J		18		YD157-YR328
1101Z				BN	0-0	27-25-11	D40842J	S/R			D40268J	S/R			YC053-YD155
1101Z				BN	0-0	27-23-11	D40842J	S/R			D40268J	S/R			YD157-YR328
1102	20	GE		BP	7-0	27-25-11	D40842J	20			D40268J		19		YC053-YD155
1102	20	VF		BP	6-3	27-23-11	D40842J	20			D40268J		19		YD157-YR328
1102Z				BP	0-0	27-25-11	D40842J	S/R			D40268J	S/R			YC053-YD155
1102Z				BP	0-0	27-23-11	D40842J	S/R			D40268J	S/R			YD157-YR328
2001B	20	GQ		GA	7-0	27-25-11	D40842J	31			D40268J		17		YC053-YD155
2001B	20	VG		GA	6-3	27-25-11	D40842J	31			D40268J		17		YD157-YR328
2001R	20	GQ		GA	0-0	27-25-11	D40842J	30			D40268J		16		YC053-YD155
2001R	20	VG		GA	0-0	27-25-11	D40842J	30			D40268J		16		YD157-YR328
2001Z				GA	0-0	27-25-11	D40842J	S/R			D40268J	S/R			YC053-YR328
2202B	20	Y6		KB	6-2	27-28-11	D40842J	16			D40268J		8		YC053-YD153
2202B	20	Y6		KB	6-3	27-28-11	D40842J	16			D40268J		8		YD154-YR328
2202R	20	Y6		KB	0-0	27-28-11	D40842J	17			D40268J		9		YC053-YR328
2202Z				KB	0-0	27-28-11	D40842J	S/R			D40268J	S/R			YC053-YR328
2203B	20	Y6		KC	6-2	27-28-11	D40842J	18			D40268J		1		YC053-YD153
2203B	20	Y6		KC	6-3	27-28-11	D40842J	18			D40268J		1		YD154-YR328
2203R	20	Y6		KC	0-0	27-28-11	D40842J	19			D40268J		2		YC053-YR328
2203Z				KC	0-0	27-28-11	D40842J	S/R			D40268J	S/R			YC053-YR328
3203B	20	VH		YC	6-2	27-28-11	D40842J	14			D40268J		5		YC053-YD153
3203B	20	VH		YC	6-3	27-28-11	D40842J	14			D40268J		5		YD154-YR328
3203R	20	VH		YC	0-0	27-28-11	D40842J	15			D40268J		4		YC053-YR328
3203Y	20	VH		YC	0-0	27-28-11	D40842J	27			D40268J		3		YC053-YR328
3203Z				YC	0-0	27-28-11	D40842J	S/R			D40268J	S/R			YC053-YR328
A-A					0-0	31-53-11	S00546	6			S00546	CAP	Y		YC053-YR328
A-B					0-0	31-53-11	S00546	5			SP00056		9		YC053-YL955, YN231-YN235
A-B					0-0	31-53-11	S00546	5			S00546	CAP	Y		YL956-YL999, YN236-YR328
A-C					0-0	31-53-11	S00546	3			SP00054		9		YC053-YL955, YN231-YN235
A-C					0-0	31-53-11	S00546	3			S00546	CAP	Y		YL956-YL999, YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W4130

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W4134	286A4134				AB1050R TO VERTICAL STAB (continued)										
A-D				0-0	31-53-11	S00546		2		S00546	CAP	Y		YC053-YL955, YN231-YN235	
A-D				0-0	31-53-11	S00546		2		SP00056		9		YL956-YL999, YN236-YR328	
A-E				0-0	31-53-11	S00546		4		GD00078	DC..	1		YC053-YD153	
A-E				0-0	31-53-11	S00546		4		GD00024	DC..	1		YD154-YL955, YN231-YN235	
A-E				0-0	31-53-11	S00546		4		S00546	CAP	Y		YL956-YL999, YN236-YR328	
A-F				0-0	31-53-11	S00546		1		SP00058		9		YC053-YL955, YN231-YN235	
A-F				0-0	31-53-11	S00546		1		GD00024	DC..	1		YL956-YL999, YN236-YR328	
B-A				0-0	31-53-11	S00132		6		S00132	CAP	Y		YC053-YR328	
B-B				0-0	31-53-11	S00132		5		SP00056		9		YC053-YL955, YN231-YN235	
B-B				0-0	31-53-11	S00132		5		S00132	CAP	Y		YL956-YL999, YN236-YR328	
B-C				0-0	31-53-11	S00132		3		SP00058		9		YC053-YL955, YN231-YN235	
B-C				0-0	31-53-11	S00132		3		S00132	CAP	Y		YL956-YL999, YN236-YR328	
B-D				0-0	31-53-11	S00132		2		S00132	CAP	Y		YC053-YL955, YN231-YN235	
B-D				0-0	31-53-11	S00132		2		SP00056		9		YL956-YL999, YN236-YR328	
B-E				0-0	31-53-11	S00132		4		GD00078	DC..	1		YC053-YD153	
B-E				0-0	31-53-11	S00132		4		GD00024	DC..	1		YD154-YL955, YN231-YN235	
B-E				0-0	31-53-11	S00132		4		S00132	CAP	Y		YL956-YL999, YN236-YR328	
B-F				0-0	31-53-11	S00132		1		GD00078	DC..	1		YC053-YD153	
B-F				0-0	31-53-11	S00132		1		GD00024	DC..	1		YD154-YR328	
C-A				0-0	31-53-11	S01184		6		S01184	CAP	Y		YL956-YL999, YN236-YR328	
C-B				0-0	31-53-11	S01184		5		S01184	CAP	Y		YL956-YL999, YN236-YR328	
C-C				0-0	31-53-11	S01184		3		SP00058		9		YL956-YL999, YN236-YR328	

WIRE LIST

D280A108

91-21-11

Section W4130

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W4134	286A4134				AB1050R TO VERTICAL STAB (continued)										
C-D				0-0	31-53-11	S01184		2		S01184	CAP	Y		YL956-YL999, YN236-YR328	
C-E				0-0	31-53-11	S01184		4		S01184	CAP	Y		YL956-YL999, YN236-YR328	
C-F				0-0	31-53-11	S01184		1		GD00024	DC..	1		YL956-YL999, YN236-YR328	
D-A				0-0	31-53-11	S01183		6		S01183	CAP	Y		YL956-YL999, YN236-YR328	
D-B				0-0	31-53-11	S01183		5		S01183	CAP	Y		YL956-YL999, YN236-YR328	
D-C				0-0	31-53-11	S01183		3		SP00054		9		YL956-YL999, YN236-YR328	
D-D				0-0	31-53-11	S01183		2		S01183	CAP	Y		YL956-YL999, YN236-YR328	
D-E				0-0	31-53-11	S01183		4		S01183	CAP	Y		YL956-YL999, YN236-YR328	
D-F				0-0	31-53-11	S01183		1		SP00058		9		YL956-YL999, YN236-YR328	

WIRE LIST

D280A108

91-21-11

Section W4130

Page 4 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				Effectivity
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	
W4140	286A4140			PASS CAB TEMP SENSOR (M1719) TO STA 405 (CEILING) NB2											
5501	22	PA		5-3	21-61-22	D10962		3			D41436J	1		YN231-YN260	
5502	22	PA		5-3	21-61-22	D10962		1			D41436J	2		YN231-YN260	
5503	22	PA		7-1	21-61-22	D10960		1			D41436J	3		YN231-YN260	
5504	20	PA		7-1	21-61-22	D10960		2			D41436J	4		YN231-YN260	
5505	20	PA		7-1	21-61-22	D10960		3			D41436J	5		YN231-YN260	
5506	20	PA		5-3	21-61-51	D10964		B			D41436J	6		YN231-YN260	
5507	20	PA		5-3	21-61-51	D10964		A			D41436J	7		YN231-YN260	
W4142	286A4142			EMERGENCY EXIT LIGHT - RIGHT											
0001	16	PA		3-0	33-51-11	D10748		1	16		GD03924	DC..	1	YC051-YN260	
0002	20	PA		1-11	33-51-11	D10748		2			SM00001		S	YC051-YD157	
0002	20	PA		1-11	33-51-11	D10748		2			SM00001		9	YD158-YN260	
0003	22	PA		1-11	33-51-11	D10748		3			SM00003		S	YC051-YD157	
0003	22	PA		1-11	33-51-11	D10748		3			SM00003		9	YD158-YN260	
0004	22	PA		1-11	33-51-11	D10748		4			SM00004		S	YC051-YD157	
0004	22	PA		1-11	33-51-11	D10748		4			SM00004		9	YD158-YN260	
0006	20	PA		0-7	33-51-11	D10748		5			D10748	6		YC051-YN260	
0007	20	PA		3-1	33-51-11	D10748		7			GD03924	ST..	1	YC051-YN260	
0009	20	PA		4-10	33-51-12	D10748		9			D40042P	3		YC051-YL999	
0009	20	PA		4-9	33-51-12	D10748		9			D40040P	3		YN231-YN260	
0009	20	PA		7-11	33-51-12	D14812		9			D40040P	3		YN501	
0009	20	PA		7-9	33-51-12	D14812		9			D40042P	3		YR301-YR328	
0010	20	PA		38-1	33-51-21	D10748		10			D10126	1		YC051-YC060	
0010	20	PA		38-1	33-51-21	D10748		12			D10126	1		YC061-YD157	
0010	16	PA		3-7	33-51-21	D10748		12	16		D40096J	4	16	YD158-YN260	
0010	16	PA		6-5	33-51-21	D14812		12	16		D40096J	4	16	YN501	
0010	16	PA		6-6	33-51-21	D14812		12	16		D40096J	4	16	YR301-YR328	
0011	18	PA		16-6	33-51-12	D10748		11	18		D11072	1		YC051-YD157, YN231-YN260	
0011	20	PA		1-0	33-51-12	D10748		11			SM00111		9	YD158-YL999	
0011	18	PA		18-10	33-51-12	D14812		11	18		D11072	1		YN501	
0011	20	PA		1-0	33-51-12	D14812		11			SM00011		9	YR301-YR328	
0012	20	PA		19-11	33-51-21	D10748		12			D03658	=1	VY	YC051-YC052	
0012	20	PA		19-9	33-51-21	D10748		12			D03658	=1	VY	YC053-YC060	
0012	20	PA		19-9	33-51-21	D10748		10			D03658	=1	VY	YC061-YD170, YN231-YN260	
0012	20	PA		19-9	33-51-21	D10748		15			D03658	=1	VY	YL951-YL999	
0012	20	PA		18-2	33-51-21	D14812		10			D03658	=1	VY	YN501	
0012	20	PA		18-2	33-51-21	D14812		15			D03658	=1	VY	YR301-YR328	

WIRE LIST

D280A108

91-21-11

Section W4140

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4142		286A4142			EMERGENCY EXIT LIGHT - RIGHT (continued)											
0014		20		PA		3-5	33-51-12	D10748				D07184J	= 1	VS		YD158-YN260
0015		20		PA		14-10	33-51-12	D10748				D11092	1			YC051-YD170
0016		20		PA		21-1	33-51-12	D10748				D12246	1			YC051-YD157
0016		20		PA		23-4	33-51-12	D10748				D11094	1			YN231-YN260
0019		20		PA		5-2	33-51-12	D14696				D07192J	= 1	VY		YN501
0020		20		PA		2-11	33-51-12	D14696				GD03872	DC..	1		YN501
0021		16		PA		3-3	33-51-12	D14700				D07194J	= 1	VY		YN501
0022		20		PA		1-11	33-51-11	D10748				SM00001		S		YC051-YD157
0022		20		PA		1-11	33-51-11	D10748				SM00001		9		YD158-YN260
0023		16		PA		5-4	33-51-12	D14700				GD03798	DC..	1		YN501
0024		20		PA		0-7	33-51-11	D10748				D10748	24			YC051-YN260
0025		20		PA		2-2	52-71-13	D40292J				D40096J	9			YC051-YL999, YR301-YR328
0026		20		PA		2-2	52-71-13	D40096J				D40292J	3			YC051-YL999, YR301-YR328
0027		20		PA		46-4	52-71-13	D40292J				D46438J	2			YC051-YL999, YR301-YR328
0030		16		PA		16-0	33-51-12	D11072				SM00111		9		YD158-YL999
0030		16		PA		18-4	33-51-12	D11072				SM00011		9		YR301-YR328
0031		20		PA		3-10	33-51-11	D40296J				SM00001		S		YC051-YD157
0031		20		PA		3-10	33-51-11	D40296J				SM00001		9		YD158-YL999, YR301-YR328
0031		20		PA		3-9	33-51-11	D40296J				SM00001		9		YN231-YN501
0032		22		PA		3-10	33-51-11	D40296J				SM00004		S		YC051-YD157
0032		22		PA		3-10	33-51-11	D40296J				SM00004		9		YD158-YL999, YR301-YR328
0032		22		PA		3-9	33-51-11	D40296J				SM00004		9		YN231-YN501
0033		22		PA		3-10	33-51-11	D40296J				SM00003		S		YC051-YD157
0033		22		PA		3-10	33-51-11	D40296J				SM00003		9		YD158-YL999, YR301-YR328
0033		22		PA		3-9	33-51-11	D40296J				SM00003		9		YN231-YN501
0034		18		PA		32-9	33-41-11	D40296J				L00035	PWR	E		YC051-YL999, YR301-YR328
0034		18		PA		23-8	33-41-11	D40296J				L00035	PWR	E		YN231-YN501
0035		20		PA		48-9	33-51-11	D40296J				SM00015		S		YC051-YD157
0035		20		PA		48-9	33-51-11	D40296J				SM00015		9		YD158-YL999
0035		20		PA		30-8	33-51-11	D40296J				SM00005		9		YN231-YN501
0035		20		PA		49-2	33-51-11	D40296J				SM00015		9		YR301-YR328
0036		20		PA		4-2	SPARE	D40296J				D10748	CAP	Y		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W4140

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4142	286A4142				EMERGENCY EXIT LIGHT - RIGHT (continued)											
0036	20		PA		4-0	SPARE		D40296J		4		D10748		CAP	Y	YD158-YN260
0036	20		PA		6-10	SPARE		D40296J		4		D14812		CAP	Y	YN501
0036	20		PA		6-11	SPARE		D40296J		4		D14812		CAP	Y	YR301-YR328
0037	20		PA		90-11	SPARE		D40296J		7		D10744		CAP	Y	YC051-YD157
0037	20		PA		90-9	SPARE		D40296J		7		D10744		CAP	Y	YD158-YL999, YR301-YR328
0037	20		PA		71-7	SPARE		D40296J		7		D10744		CAP	Y	YN231-YN260
0037	20		PA		71-9	SPARE		D40296J		7		D10744		CAP	Y	YN501
0038	20		PA		4-2	SPARE		D40296J		15		D10748		CAP	Y	YC051-YD157
0038	20		PA		4-0	SPARE		D40296J		15		D10748		CAP	Y	YD158-YN260
0038	20		PA		6-10	SPARE		D40296J		15		D14812		CAP	Y	YN501
0038	20		PA		6-11	SPARE		D40296J		15		D14812		CAP	Y	YR301-YR328
0039	20		PA		90-11	SPARE		D40296J		CAP	Y	D10744		CAP	Y	YC051-YD151
0039	20		PA		91-1	SPARE		D40296J		CAP	Y	D10744		CAP	Y	YD152-YD157
0039	20		PA		90-9	SPARE		D40296J		CAP	Y	D10744		CAP	Y	YD158-YL999, YR301-YR328
0039	20		PA		71-7	SPARE		D40296J		CAP	Y	D10744		CAP	Y	YN231-YN260
0039	20		PA		71-11	SPARE		D40296J		CAP	Y	D10744		CAP	Y	YN501
0041	16		PA		4-5	33-51-12		D40096J		1	16	SM00121			9	YD158-YL999, YR301-YR328
0042	20		PA		1-7	33-51-11		SM00001		S		SM00002			S	YC051-YD157
0042	20		PA		1-7	33-51-11		SM00001		9		SM00002			9	YD158-YR328
0043	22		PA		49-8	33-51-11		SM00003		S		SM00013			S	YC051-YD157
0043	22		PA		49-8	33-51-11		SM00003		9		SM00013			9	YD158-YL999
0043	22		PA		50-0	33-51-11		SM00003		9		SM00013			9	YR301-YR328
0044	22		PA		41-3	33-51-11		SM00004		S		SM00014			S	YC051-YD157
0044	22		PA		41-3	33-51-11		SM00004		9		SM00014			9	YD158-YL999, YR301-YR328
0045	20		PA		39-5	33-51-11		SM00005		S		SM00015			S	YC051-YD157
0045	20		PA		39-5	33-51-11		SM00005		9		SM00015			9	YD158-YL999
0045	20		PA		39-9	33-51-11		SM00005		9		SM00015			9	YR301-YR328
0046	20		PA		43-10	33-51-11		SM00005		S		SM00006			S	YC051-YD157
0046	20		PA		43-10	33-51-11		SM00005		9		SM00006			9	YD158-YL999, YR301-YR328
0046	20		PA		40-11	33-51-11		SM00005		9		SM00006			9	YN231-YN501
0047	22		PA		39-5	33-51-11		SM00007		S		SM00013			S	YC051-YD157
0047	22		PA		39-5	33-51-11		SM00007		9		SM00013			9	YD158-YL999
0047	22		PA		31-7	33-51-11		SM00007		9		SM00003			9	YN231-YN501
0047	22		PA		39-9	33-51-11		SM00007		9		SM00013			9	YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4140

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4142	286A4142				EMERGENCY EXIT LIGHT - RIGHT (continued)										
0048	22		PA		50-5	33-51-11	SM00008		S		SM00014		S		YC051-YD157
0048	22		PA		50-5	33-51-11	SM00008		9		SM00014		9		YD158-YL999, YR301-YR328
0048	22		PA		31-7	33-51-11	SM00008		9		SM00004		9		YN231-YN501
0049	20		PA		33-1	33-51-11	SM00009		S		SM00002		S		YC051-YD157
0049	20		PA		33-1	33-51-11	SM00009		9		SM00002		9		YD158-YL999, YR301-YR328
0049	20		PA		4-5	33-51-11	D40096J	13			SM00002		9		YN231-YN501
0050	20		PA		2-4	33-51-21	D10126	4			GD03358	DC..	1		YC051-YD157
0051	18		PA		2-10	33-51-12	D11072	2			GD03880	DC..	1		YC051-YL999, YR301-YR328
0051	18		PA		2-8	33-51-12	D11072	2			GD03880	DC..	1		YN231-YN501
0052	20		PA		4-1	33-51-21	D03660	=1	VG		GD10086	DC..	1		YC051-YL999, YR301-YR328
0052	20		PA		4-0	33-51-21	D03660	=1	VG		GD10086	DC..	1		YN231-YN501
0055	20		PA		6-7	33-51-12	D11092	2			GD03858	DC..	1A		YC051-YD170
0056	20		PA		13-7	33-51-12	D11094	2			GD03750	DC..	1		YN231-YN260
0057	22		PA		3-5	33-51-11	D40096J	14			SM00003		9		YD158-YL999, YR301-YR328
0057	22		PA		3-4	33-51-11	D40096J	12			SM00003		9		YN231-YN501
0058	22		PA		3-5	33-51-11	D40096J	11			SM00004		9		YD158-YL999, YR301-YR328
0058	22		PA		3-4	33-51-11	D40096J	11			SM00004		9		YN231-YN501
0059	20		PA		3-8	33-51-12	D40042P	4			GD03924	DC..	1		YC051-YL999, YR301-YR328
0059	20		PA		1-11	33-51-12	D40040P	4			GD04168	DC..	1		YN231-YN501
0060	20		PA		30-9	33-51-11	D40096J	13			SM00009		9		YD158-YL999, YR301-YR328
0061	16		PA		4-6	33-51-12	SP03480		S		SM00113		9		YD158-YL999
0064	20		PA		13-11	33-51-12	D14690	A			D14812	16			YN501
0064	20		PA		14-0	33-51-12	D14690	A			D14812	14			YR301-YR328
0065	18		CQ		2-5	35-21-21	D40040P	5			D07170P	=1	VG		YC051-YL999, YR301-YR328
0065	18		CQ		2-4	35-21-21	D40040P	5			D07170P	=1	VG		YN231-YN501
0066	18		CQ		6-5	35-21-21	D40040P	6			GD03924	DC..	1		YC051-YL999, YR301-YR328
0066	18		CQ		6-3	35-21-21	D40040P	6			GD03924	DC..	1		YN231-YN501
0070	20		PA		4-3	33-51-12	D14690	B			GD03854	DC..	1		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W4140

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4142	286A4142				EMERGENCY EXIT LIGHT - RIGHT (continued)										
0071	18		PA		4-6	33-41-11	L00035	RTN	E		GD08004	AC..	1		YC051-YL999, YR301-YR328
0071	18		PA		3-2	33-41-11	L00035	RTN	E		GD03878	AC..	1		YN231-YN501
0072	18		PA		4-5	33-41-11	L00035	CASE	E		GD08004	ST..	1		YC051-YL999, YR301-YR328
0072	18		PA		3-0	33-41-11	L00035	CASE	E		GD03878	ST..	1		YN231-YN501
0073	16		PA		5-1	33-51-12	D12044		2		GD08016	DC..	1		YC051-YL999
0074	16		PA		21-10	33-51-12	SM00028		9		D12044		1		YC051-YD157
0075	16		PA		1-0	33-51-12	SM00028		9		D40086J		6		YC051-YD157
0076	20		PA		5-2	33-51-12	D12246		2		GD03862	DC..	1		YC051-YL999
0077	18		CQ		5-1	35-21-31	D40042P		5		D07180P	=1	VG		YC051-YL999, YR301-YR328
0077	18		CQ		5-2	35-21-31	D40042P		5		D07180P	=1	VG		YN231-YN501
0078	18		CQ		3-8	35-21-31	D40042P		6		GD03924	DC..	1		ALL
0080	16		PA		3-5	33-51-21	SM00016		S		D40098P		3		YC051-YC052
0080	16		PA		14-8	33-51-21	SM00016		S		D40098P		3		YC053-YD157
0081	16		PA		16-10	33-51-21	D12430	=1	VY		SM00016		S		YC051-YC052
0081	16		PA		27-7	33-51-21	D12430	=1	VY		SM00016		S		YC053-YD157
0082	16		PA		15-10	33-51-21	D12432	=1	VG		GD03996	DC..	1		YC051-YD157
0082	20		PA		15-10	33-51-22	D12432	=1	VG		GD03996	DC..	1		YD158-YL999, YR301-YR328
0084	16		PA		15-8	33-51-21	D40098P		8		D12064	=1	VY		YC051-YD157
0084	20		PA		15-8	33-51-21	D40098P		8		D12064	=1	VY		YD158-YL999
0084	20		PA		16-0	33-51-21	D40098P		8		D12064	=1	VY		YR301-YR328
0086	16		PA		3-10	33-51-21	D12066	=1	VG		GD08002	DC..	1		YC051-YD157
0086	20		PA		3-10	33-51-21	D12066	=1	VG		GD08002	DC..	1		YD158-YL999, YR301-YR328
0092	12		PA		21-1	33-51-14	SM00031		9		SP00544		S		YC051-YL999, YR301-YR328
0093	20		PA		2-2	52-71-13	D40292J		4		D40096J		5		YC051-YL999, YR301-YR328
0093	20		PA		2-1	52-71-13	D40292J		4		D40096J		5		YN231-YN501
0094	20		PA		2-2	52-71-13	D40292J		6		D40096J		7		YC051-YL999, YR301-YR328
0094	20		PA		2-1	52-71-13	D40292J		6		D40096J		7		YN231-YN501
0096	20		PA		2-2	52-71-14	D40292J		8		D40096J		8		YC051-YL999, YR301-YR328
0096	20		PA		2-1	52-71-14	D40292J		8		D40096J		8		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W4140

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4142	286A4142			EMERGENCY EXIT LIGHT - RIGHT (continued)											
0098	20		PA		44-1	52-71-13	D40292J		2		D46440J		2		YC051-YL999, YR301-YR328
0098	20		PA		39-2	52-71-13	D40292J		2		D46440J		2		YN231-YN501
0101	16		PA		3-0	33-51-11	D10750		1	16	GD04168	DC..	1		YC051-YD170, YN231-YN501
0101	16		PA		3-2	33-51-11	D10750		1	16	GD04168	DC..	1		YL951-YL999, YR301-YR328
0102	20		PA		1-1	33-51-11	D10750		2		SM00002		S		YC051-YD157
0102	20		PA		1-1	33-51-11	D10750		2		SM00002		9		YD158-YN501
0102	20		PA		1-3	33-51-11	D10750		2		SM00002		9		YR301-YR328
0103	22		PA		2-1	33-51-11	D10750		3		SM00003		S		YC051-YD157
0103	22		PA		2-1	33-51-11	D10750		3		SM00003		9		YD158-YN501
0103	22		PA		2-3	33-51-11	D10750		3		SM00003		9		YR301-YR328
0104	22		PA		2-1	33-51-11	D10750		4		SM00004		S		YC051-YD157
0104	22		PA		2-1	33-51-11	D10750		4		SM00004		9		YD158-YN501
0104	22		PA		2-3	33-51-11	D10750		4		SM00004		9		YR301-YR328
0106	20		PA		0-7	33-51-11	D10750		5		D10750		6		ALL
0107	20		PA		3-6	33-51-11	D10750		7		GD04168	ST..	1		YC051-YL999
0107	20		PA		3-5	33-51-11	D10750		7		GD04168	ST..	1		YN231-YN501
0107	20		PA		3-8	33-51-11	D10750		7		GD04168	ST..	1		YR301-YR328
0109	20		PA		3-10	33-51-12	D10750		9		D40040P		3		YC051-YL999
0109	20		PA		6-8	33-51-12	D10750		9		D40042P		3		YN231-YN501
0109	20		PA		4-0	33-51-12	D10750		9		D40040P		3		YR301-YR328
0110	20		PA		2-1	33-51-21	D10750		10		SM00090		S		YC051-YC060
0110	20		PA		2-1	33-51-21	D10750		12		SM00090		S		YC061-YD157
0110	16		PA		4-11	33-51-21	D10750		12	16	D40096J		6	16	YD158-YN260
0110	20		PA		4-11	33-51-21	D10750		12		D40096J		6		YN501
0110	20		PA		5-1	33-51-21	D10750		12		D40096J		6		YR301-YR328
0111	18		PA		4-11	33-51-12	D10750		11	18	D40096J		1	18	YC051-YD157, YN231-YN501
0111	20		PA		1-0	33-51-12	D10750		11		SM00121		9		YD158-YL999, YR301-YR328
0112	20		PA		20-1	33-51-21	D10750		12		D03662	= 1	VY		YC051-YC052
0112	20		PA		20-9	33-51-21	D10750		12		D03662	= 1	VY		YC053-YC060
0112	20		PA		20-9	33-51-21	D10750		10		D03662	= 1	VY		YC061-YD170, YN231-YN501
0112	20		PA		20-9	33-51-21	D10750		15		D03662	= 1	VY		YL951-YL999
0112	20		PA		21-0	33-51-21	D10750		15		D03662	= 1	VY		YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4140

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4142	286A4142				EMERGENCY EXIT LIGHT - RIGHT (continued)										
0113	20		PA		5-0	33-51-12	D10750	13			SP03480		S		YC051-YD157, YN231-YN260
0113	20		PA		1-0	33-51-12	D10750	13			SM00113		9		YD158-YL999
0113	20		PA		5-0	33-51-12	D10750	13			SP03480		9		YN501
0113	20		PA		5-2	33-51-12	D10750	13			SP03480		9		YR301-YR328
0114	20		PA		5-4	33-51-12	D10750	14			D40296J	38			YC051-YN501
0114	20		PA		6-0	33-51-12	D10750	14			D40296J	38			YR301-YR328
0115	20		PA		4-11	33-51-12	D10750	15			D40096J	2			YC051-YD170
0116	20		PA		4-11	33-51-12	D10750	16			D40096J	3			YN231-YN501
0117	20		PA		3-5	33-51-21	SM00090		S		D40096J	6			YC051-YD157
0122	20		PA		1-1	33-51-11	D10750	22			SM00002		S		YC051-YD157
0122	20		PA		1-1	33-51-11	D10750	22			SM00002		9		YD158-YN501
0122	20		PA		1-3	33-51-11	D10750	22			SM00002		9		YR301-YR328
0124	20		PA		0-7	33-51-11	D10750	20			D10750	24			ALL
0150	20		PA		2-4	33-51-21	D10126	5			GD03358	DC..	1		YC051-YD157
0152	20		PA		2-6	33-51-21	D03664	=1	VG		GD03782	DC..	1		ALL
0153	20		PA		37-11	33-51-21	D10126	2			SM00090		S		YC051-YD157
0159	20		PA		1-11	33-51-12	D40040P	4			GD04168	DC..	1		YC051-YL999, YR301-YR328
0159	20		PA		3-8	33-51-12	D40042P	4			GD03924	DC..	1		YN231-YN501
0201	16		PA		3-0	33-51-11	D12004	1	16		GD08006	DC..	1		YC051-YL999, YR301-YR328
0201	16		PA		3-0	33-51-11	D10714	1	16		GD03972	DC..	1		YN231-YN501
0202	20		PA		0-11	33-51-11	D12004	2			SM00005		S		YC051-YD157
0202	20		PA		0-11	33-51-11	D12004	2			SM00005		9		YD158-YL999, YR301-YR328
0202	20		PA		11-7	33-51-11	D10714	2			SM00005		9		YN231-YN501
0203	22		PA		0-11	33-51-11	D12004	3			SM00007		S		YC051-YD157
0203	22		PA		0-11	33-51-11	D12004	3			SM00007		9		YD158-YL999, YR301-YR328
0203	22		PA		11-7	33-51-11	D10714	3			SM00007		9		YN231-YN501
0204	22		PA		44-3	33-51-11	D12004	4			SM00008		S		YC051-YD157
0204	22		PA		44-3	33-51-11	D12004	4			SM00008		9		YD158-YL999, YR301-YR328
0204	22		PA		11-7	33-51-11	D10714	4			SM00008		9		YN231-YN501
0206	20		PA		0-7	33-51-11	D12004	5			D12004	6			YC051-YL999, YR301-YR328
0206	20		PA		0-7	33-51-11	D10714	5			D10714	6			YN231-YN501

WIRE LIST

D280A108

91-21-11
Section W4140
Page 7
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4142	286A4142				EMERGENCY EXIT LIGHT - RIGHT (continued)										
0207	20		PA		3-0	33-51-11	D12004	7			GD08006	ST..	1		YC051-YL999, YR301-YR328
0207	20		PA		1-10	33-51-11	D10714	7			GD03972	ST..	1		YN231-YN501
0209	20		PA		32-6	33-51-14	D12004	9			D12488	1			YC051-YD157
0209	20		PA		35-5	33-51-22	D12004	9			D12430	=1	VY		YD158-YD170
0209	20		PA		35-5	33-51-22	D12430	=1	VY		D12004	9			YL951-YL999
0209	20		PA		1-0	33-51-13	D10714	9			SM00209		9		YN231-YN260
0209	16		PA		14-9	33-51-13	D10714	9	16		SM00011		9		YN501
0209	20		PA		35-5	33-51-22	D12430	=1	VY		D12004	10			YR301-YR328
0210	20		PA		21-6	33-51-22	D12004	10			SP00642		S		YC051-YD157
0210	20		PA		1-0	33-51-22	D12004	12			SM00210		9		YD158-YL999
0211	16		PA		1-0	33-51-14	D12004	11	16		SM00031		9		YC051-YL999, YR301-YR328
0211	20		PA		1-0	33-51-13	D10714	11			SM00211		9		YN231-YN260
0211	16		PA		24-4	33-51-13	D10714	11	16		D11076	1			YN501
0212	16		PA		1-0	33-51-14	D12004	12	16		SM00024		9		YC051-YD157
0212	16		PA		1-0	33-51-14	D12004	10	16		SM00024		9		YD158-YL999
0212	20		PA		4-7	33-51-21	D10714	10			D03666	=1	VY		YN231-YN260
0212	20		PA		4-7	33-51-21	D10714	13			D03666	=1	VY		YN501
0212	16		PA		1-0	33-51-14	D12004	9	16		SM00024		9		YR301-YR328
0213	20		PA		11-6	33-51-14	D12004	13			D12022	1			YC051-YL999
0213	20		PA		27-1	33-51-21	D10714	13			D12392	=1	VY		YN231-YN260
0214	20		PA		20-1	33-51-14	D12004	14			D12024	1			YC051-YL999
0215	20		PA		20-5	33-51-14	D12004	15			D12026	1			YC051-YL999
0215	20		PA		10-11	33-51-13	D10714	15			D11102	1			YN231-YN260
0216	20		PA		26-10	33-51-14	D12004	16			D12020	1			YC051-YL999
0216	20		PA		19-6	33-51-13	D10714	16			D11328	1			YN231-YN260
0222	20		PA		0-11	33-51-11	D12004	22			SM00005		S		YC051-YD157
0222	20		PA		0-11	33-51-11	D12004	22			SM00005		9		YD158-YL999, YR301-YR328
0222	20		PA		11-7	33-51-11	D10714	22			SM00005		9		YN231-YN501
0224	20		PA		0-7	33-51-11	D12004	20			D12004	24			YC051-YL999, YR301-YR328
0224	20		PA		0-7	33-51-11	D10714	20			D10714	24			YN231-YN501
0230	16		PA		21-1	33-51-22	SM00210		9		SP00642		S		YD158-YD170
0230	16		PA		21-1	33-51-22	SP00642		S		SM00210		9		YL951-YL999
0231	16		PA		1-0	33-51-14	D12018	1			SM00026		9		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4140

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W4142	286A4142	EMERGENCY EXIT LIGHT - RIGHT (continued)													
0232	14	PA	32-8	33-51-14	SM00024		9		SM00026		9		YC051-YL999, YR301-YR328		
0234	18	PA	8-5	33-51-12	D07198P	= 1	VR		D11098	1			YN231-YN260		
0251	16	PA	1-9	33-51-13	D11076		2		GD03802	DC..	1		YN231-YN501		
0252	16	PA	1-11	33-51-14	D12018		2		GD03802	DC..	1		YC051-YL999, YR301-YR328		
0252	20	PA	4-3	33-51-21	D03668	= 1	VG		GD03972	DC..	1		YN231-YN501		
0253	20	PA	5-5	33-51-14	D12022		2		GD03806	DC..	1		YC051-YL999		
0254	20	PA	4-9	33-51-14	D12024		2		GD08022	DC..	1		YC051-YL999		
0254	18	PA	6-2	33-51-12	D11098		2		GD03872	DC..	1		YN231-YN260		
0255	20	PA	2-6	33-51-14	D12026		2		GD04008	DC..	1		YC051-YL999		
0255	20	PA	3-3	33-51-13	D11102		2		GD03798	DC..	1		YN231-YN260		
0256	20	PA	3-8	33-51-14	D12020		2		GD03996	DC..	1		YC051-YL999		
0256	20	PA	4-7	33-51-13	D11328		2		GD03804	DC..	1		YN231-YN260		
0257	20	PA	4-11	33-51-14	D12488		2		GD04002	DC..	1		YC051-YL999		
0259	16	PA	24-4	33-51-13	D11076		1		SM00211		9		YN231-YN260		
0260	16	PA	14-9	33-51-13	SM00209		9		SM00011		9		YN231-YN260		
0262	16	PA	3-7	33-51-13	D12460	= 1	VY		SM00011		9		YN231-YN501		
0263	16	PA	3-8	33-51-13	D12464		1		SM00011		9		YN231-YN260		
0264	16	PA	3-4	33-51-13	D12464		2		GD03794	DC..	1		YN231-YN260		
0265	20	PA	4-7	33-51-21	D12394	= 1	VG		GD03802	DC..	1		YN231-YN260		
0265	20	PA	4-7	33-51-22	D12394	= 1	VG		GD03802	DC..	1		YN501		
0269	16	PA	3-4	33-51-13	D12462	= 1	VG		GD03794	DC..	1		YN231-YN501		
0270	20	PA	18-1	33-51-22	D12392	= 1	VY		D46440J		3		YN501		
0301	16	PA	2-0	33-51-11	D12010		1	16	GD08002	DC..	1		YC051-YL999, YR301-YR328		
0302	20	PA	1-0	33-51-11	D12010		2		SM00015		S		YC051-YD157		
0302	20	PA	1-0	33-51-11	D12010		2		SM00015		9		YD158-YL999, YR301-YR328		
0303	22	PA	1-0	33-51-11	D12010		3		SM00013		S		YC051-YD157		
0303	22	PA	1-0	33-51-11	D12010		3		SM00013		9		YD158-YL999, YR301-YR328		
0304	22	PA	12-2	33-51-11	D12010		4		SM00014		S		YC051-YD157		
0304	22	PA	12-2	33-51-11	D12010		4		SM00014		9		YD158-YL999		
0304	22	PA	12-7	33-51-11	D12010		4		SM00014		9		YR301-YR328		
0306	20	PA	0-7	33-51-11	D12010		6		D12010		5		YC051-YL999, YR301-YR328		
0307	20	PA	2-0	33-51-11	D12010		7		GD08002	ST..	1		YC051-YL999, YR301-YR328		

WIRE LIST

D280A108

91-21-11

Section W4140

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4142		286A4142			EMERGENCY EXIT LIGHT - RIGHT (continued)											
0309		20		PA		15-1	33-51-13	D12010		9		D40098P		6		YC051-YL999
0309		20		PA		15-6	33-51-13	D12010		9		D40098P		6		YR301-YR328
0310		16		PA		1-0	33-51-13	D12010		10	16	SM00048		9		YC051-YD157
0311		20		PA		23-6	33-51-21	D12010		11		D03666	= 1	VY		YC051-YL999
0311		20		PA		23-10	33-51-21	D12010		11		D03666	= 1	VY		YR301-YR328
0312		16		PA		12-2	33-51-21	D12010		12	16	SM00016		S		YC051-YC052
0312		16		PA		1-0	33-51-21	D12010		12	16	SM00016		S		YC053-YD157
0312		20		PA		15-1	33-51-21	D12010		12		D40098P		3		YD158-YL999
0312		20		PA		15-6	33-51-21	D12010		12		D40098P		3		YR301-YR328
0313		16		PA		18-0	33-51-13	D12010		13	16	D12454	= 1	VY		YC051-YD157
0313		20		PA		1-0	33-51-13	D12010		13		SM00313		9		YD158-YL999, YR301-YR328
0314		16		PA		18-4	33-51-13	D12010		14	16	D12458		1		YC051-YD157
0314		20		PA		1-0	33-51-13	D12010		14		SM00314		9		YD158-YL999
0315		16		PA		21-4	33-51-13	D12010		15	16	D12460	= 1	VY		YC051-YD157
0315		20		PA		1-0	33-51-13	D12010		15		SM00315		9		YD158-YL999, YR301-YR328
0316		16		PA		21-7	33-51-13	D12010		16	16	D12464		1		YC051-YD157
0316		20		PA		1-0	33-51-13	D12010		16		SM00316		9		YD158-YL999
0322		20		PA		1-0	33-51-11	D12010		22		SM00015		S		YC051-YD157
0322		20		PA		1-0	33-51-11	D12010		22		SM00015		9		YD158-YL999, YR301-YR328
0324		20		PA		0-7	33-51-11	D12010		20		D12010		24		YC051-YL999, YR301-YR328
0330		16		PA		17-7	33-51-13	D12454	= 1	VY		SM00313		9		YD158-YL999
0330		16		PA		17-11	33-51-13	D12454	= 1	VY		SM00313		9		YR301-YR328
0331		14		PA		12-11	33-51-13	SM00048		9		SP00546		S		YC051-YD157
0332		14		PA		6-1	33-51-13	SP00546		S		SM00050		9		YC051-YD157
0333		16		PA		1-0	33-51-13	SM00050		9		D11098		1		YC051-YD157
0333		16		PA		27-0	33-51-12	SM00516		9		D11098		1		YD158-YL999
0333		16		PA		31-8	33-51-12	SM00516		9		D14700		A		YR301-YR328
0334		16		PA		17-10	33-51-13	D12458		1		SM00314		9		YD158-YL999
0334		20		PA		18-8	33-51-13	D14840		A		D12010		14		YR301-YR328
0335		16		PA		20-11	33-51-13	D12460	= 1	VY		SM00315		9		YD158-YL999
0335		16		PA		21-3	33-51-13	D12460	= 1	VY		SM00315		9		YR301-YR328
0336		16		PA		21-2	33-51-13	D12464		1		SM00316		9		YD158-YL999
0336		20		PA		21-11	33-51-13	D14724		A		D12010		16		YR301-YR328
0351		20		PA		11-7	33-51-21	D03668	= 1	VG		GD03798	DC..	1		YC051-YL999
0351		20		PA		9-7	33-51-21	D03668	= 1	VG		GD03794	DC..	1		YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4140

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4142		286A4142			EMERGENCY EXIT LIGHT - RIGHT (continued)											
0353		16		PA		8-3	33-51-13	D12458				GD03798	DC..	1		YC051-YL999
0353		20		PA		11-8	33-51-13	D14840		B		GD03794	DC..	1		YR301-YR328
0354		16		PA		8-0	33-51-13	D12456		=1	VG	GD03798	DC..	1		YC051-YL999
0354		16		PA		11-5	33-51-13	D12456		=1	VG	GD03794	DC..	1		YR301-YR328
0355		16		PA		4-0	33-51-13	D12464		2		GD03996	DC..	1		YC051-YL999
0355		20		PA		4-0	33-51-13	D14724		B		GD03996	DC..	1		YR301-YR328
0356		16		PA		3-9	33-51-13	D12462		=1	VG	GD03996	DC..	1		YC051-YL999, YR301-YR328
0361		16		PA		21-10	33-51-13	D11098		2		GD03868	DC..	1		YC051-YD157
0361		16		PA		21-10	33-51-12	D11098		2		GD03868	DC..	1		YD158-YL999
0361		16		PA		8-4	33-51-12	D14700		B		GD03794	DC..	1		YR301-YR328
0401		16		PA		4-6	33-51-11	D10744		1	16	GD03998	DC..	1		YC051-YN260
0401		16		PA		3-6	33-51-11	D10744		1	16	GD03998	DC..	1		YN501-YR328
0402		20		PA		1-0	33-51-11	D10744		2		SM00006		S		YC051-YD157
0402		20		PA		1-0	33-51-11	D10744		2		SM00006		9		YD158-YL999, YR301-YR328
0402		20		PA		1-1	33-51-11	D10744		2		SM00006		9		YN231-YN501
0403		22		PA		44-4	33-51-11	D10744		3		SM00007		S		YC051-YD157
0403		22		PA		44-4	33-51-11	D10744		3		SM00007		9		YD158-YL999, YR301-YR328
0403		22		PA		41-5	33-51-11	D10744		3		SM00007		9		YN231-YN501
0404		22		PA		1-0	33-51-11	D10744		4		SM00008		S		YC051-YD157
0404		22		PA		1-0	33-51-11	D10744		4		SM00008		9		YD158-YL999, YR301-YR328
0404		22		PA		41-5	33-51-11	D10744		4		SM00008		9		YN231-YN501
0406		20		PA		0-7	33-51-11	D10744		5		D10744		6		ALL
0407		20		PA		3-9	33-51-11	D10744		7		GD03998	ST..	1		YC051-YL999, YR301-YR328
0407		20		PA		4-0	33-51-11	D10744		7		GD03998	ST..	1		YN231-YN501
0408		16		PA		7-2	33-51-14	D14836		B		GD08030	DC..	1		YR301-YR328
0409		20		PA		7-4	33-51-14	D10744		9		D40046P		3		YC051-YL999, YR301-YR328
0409		20		PA		5-1	33-51-14	D10744		9		D40100P		3		YN231-YN501
0410		20		PA		6-10	33-51-22	D10744		10		D40100P		4		YC051-YC060
0410		20		PA		6-10	33-51-22	D10744		12		D40100P		4		YC061-YD157
0410		16		PA		6-10	33-51-22	D10744		12	16	D40100P		4		YD158-YL999
0410		16		PA		5-1	33-51-22	D10744		12	16	D40100P		4		YN231-YN260
0411		18		PA		13-4	33-51-14	D10744		11	18	D11084		1		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W4140

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4142	286A4142			EMERGENCY EXIT LIGHT - RIGHT (continued)											
0411	20		PA		1-0	33-51-14	D10744	11			SM00411		9		YD158-YL999, YR301-YR328
0411	18		PA		12-11	33-51-14	D10744	11	18		D11084	1			YN231-YN501
0412	20		PA		15-0	33-51-22	D10744	12			D10086	= 1	VY		YC051-YC060
0412	20		PA		15-0	33-51-22	D10744	10			D10086	= 1	VY		YC061-YL999, YR301-YR328
0412	20		PA		14-8	33-51-22	D10744	10			D10086	= 1	VY		YN231-YN501
0413	20		PA		21-11	33-51-14	D10744	13			D12012	1			YC051-YD157
0413	18		PA		14-1	33-51-14	D10744	13	18		SM00019		9		YD158-YD170
0413	18		PA		21-11	33-51-14	D10744	13	18		D12012	1			YL951-YL999
0413	20		PA		8-1	33-51-14	D10744	13			SP03484		S		YN231-YN501
0413	16		PA		19-1	33-51-14	D10744	13	16		D14836		A		YR301-YR328
0414	20		PA		8-6	33-51-14	D10744	14			D07186J	= 1	VS		YD158-YL999
0414	20		PA		7-6	33-51-14	D10744	14			D07186J	= 1	VS		YN231-YN260
0415	20		PA		10-11	33-51-14	D10744	15			D12014	1			YC051-YD170
0415	20		PA		17-1	33-51-14	D10744	15			D12488	1			YL951-YL999
0415	20		PA		27-9	33-51-14	D10744	15			D11332	1			YN231-YN260
0416	20		PA		6-10	33-51-14	D10744	16			D40100P	5			YC051-YD170
0416	20		PA		21-1	33-51-14	D10744	16			D11336	1			YN231-YN260
0422	20		PA		1-0	33-51-11	D10744	22			SM00006		S		YC051-YD157
0422	20		PA		1-0	33-51-11	D10744	22			SM00006		9		YD158-YL999, YR301-YR328
0422	20		PA		1-1	33-51-11	D10744	22			SM00006		9		YN231-YN501
0424	20		PA		0-7	33-51-11	D10744	20			D10744	24			ALL
0431	18		PA		8-10	33-51-14	D12012	1			SM00019		9		YD158-YD170
0432	20		PA		3-6	33-51-14	D12488	1			SM00019		9		YD158-YD170
0434	20		PA		2-2	52-71-14	D40096J	12			D40292J	7			YC051-YL999, YR301-YR328
0435	20		PA		49-9	52-71-14	SP01820		9		D40296J	27			YC051-YL999, YR301-YR328
0436	20		PA		6-9	52-71-14	SP01818		9		SM00056		9		YC051-YL999, YR301-YR328
0437	20		PA		50-7	52-71-14	D40292J	9			SP01822		9		YC051-YL999, YR301-YR328
0438	20		PA		15-9	52-71-14	SP01802		9		SM00056		9		YC051-YL999, YR301-YR328
0439	20		PA		16-2	52-71-14	SP01824		9		GD03794	DC..	1		YC051-YL999, YR301-YR328
0440	20		PA		48-3	52-71-14	D40292J	10			SP01826		9		YC051-YL999

WIRE LIST

D280A108

91-21-11

Section W4140

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4142	286A4142				EMERGENCY EXIT LIGHT - RIGHT (continued)										
0440	20		PA		48-7	52-71-14	D40292J	10			SP01826		9		YR301-YR328
0441	20		PA		9-2	52-71-14	SP01828		9		GD08002	DC..	1		YC051-YL999, YR301-YR328
0442	20		PA		14-1	52-71-14	D46438J	1			SP01830		9		YC051-YL999, YR301-YR328
0443	20		PA		7-10	52-71-14	SP01832		9		GD03794	DC..	1		YC051-YL999, YR301-YR328
0444	16		PA		12-10	33-51-14	D11084	1			SM00411		9		YD158-YL999, YR301-YR328
0451	18		PA		3-6	33-51-14	D11084	2			GD03810	DC..	1		YC051-YL999, YR301-YR328
0451	18		PA		3-1	33-51-14	D11084	2			GD03810	DC..	1		YN231-YN501
0452	20		PA		5-3	33-51-22	D10088	=1	VG		GD03810	DC..	1		YC051-YL999, YR301-YR328
0452	20		PA		4-9	33-51-22	D10088	=1	VG		GD03810	DC..	1		YN231-YN501
0453	20		PA		4-10	33-51-14	D12012	2			GD08030	DC..	1		YC051-YD157
0453	18		PA		4-10	33-51-14	D12012	2			GD08030	DC..	1		YD158-YL999
0455	20		PA		3-5	33-51-14	D12014	2			GD03816	DC..	1		YC051-YD170
0455	20		PA		3-4	33-51-14	D11332	2			GD03806	DC..	1		YN231-YN260
0456	20		PA		3-8	33-51-14	D11336	2			GD03808	DC..	1		YN231-YN260
0459	20		PA		3-6	33-51-14	D40046P	4			GD03772	DC..	1		YC051-YL999, YR301-YR328
0460	20		PA		15-4	52-71-14	D46440J	1			SP01814		9		YC051-YL999, YR301-YR328
0460	20		PA		16-5	52-71-14	D46440J	1			SP01814		9		YN231-YN501
0461	20		PA		7-11	52-71-14	SP01816		9		GD03802	DC..	1		YC051-YL999, YR301-YR328
0461	20		PA		9-3	52-71-14	SP01816		9		GD03802	DC..	1		YN231-YN501
0462	20		PA		44-1	52-71-14	D40296J	23			SM00056		9		YC051-YL999, YR301-YR328
0462	20		PA		43-8	52-71-14	D40296J	23			SP01802		9		YN231-YN501
0463	20		PA		53-7	52-71-14	D40296J	24			SP01804		9		YC051-YL999, YR301-YR328
0463	20		PA		43-8	52-71-14	D40296J	24			SP01804		9		YN231-YN501
0464	20		PA		54-4	52-71-14	D40292J	12			SP01806		9		YC051-YL999, YR301-YR328
0464	20		PA		44-4	52-71-14	D40292J	12			SP01806		9		YN231-YN501
0465	20		PA		9-0	52-71-14	SP01808		9		GD03996	DC..	1		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4140

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W4142	286A4142				EMERGENCY EXIT LIGHT - RIGHT (continued)											
0465	20	PA		10-10	52-71-14	SP01808			9		GD03794	DC..	1		YN231-YN501	
0466	20	PA		49-8	52-71-14	D40292J		11			SP01810		9		YC051-YL999, YR301-YR328	
0466	20	PA		40-8	52-71-14	D40292J		11			SP01810		9		YN231-YN501	
0467	20	PA		7-10	52-71-14	SP01812			9		GD03794	DC..	1		YC051-YL999, YR301-YR328	
0467	20	PA		9-5	52-71-14	SP01812			9		GD03972	DC..	1		YN231-YN501	
0473	20	PA		8-11	33-51-14	D40046P		3			D40100P		2		YN231-YN501	
0474	20	PA		3-6	33-51-14	D40046P		4			GD03772	DC..	1		YN231-YN501	
0475	22	PA		12-3	33-26-11	D40046P		5			SP03522		S		YC051-YL999, YR301-YR328	
0475	22	PA		11-4	33-26-11	D40046P		5			SP03522		S		YN231-YN501	
0476	20	PA		3-6	33-26-11	D40046P		6			GD03772	AC..	1		ALL	
0501	16	PA		2-1	33-51-11	D12002		1	16		GD08004	DC..	1		YC051-YL999, YR301-YR328	
0502	20	PA		1-3	33-51-11	D12002		2			SM00009		S		YC051-YD157	
0502	20	PA		1-3	33-51-11	D12002		2			SM00009		9		YD158-YL999	
0502	20	PA		1-2	33-51-11	D12002		2			SM00009		9		YR301-YR328	
0503	22	PA		32-9	33-51-11	D12002		3			SM00003		S		YC051-YD157	
0503	22	PA		32-9	33-51-11	D12002		3			SM00003		9		YD158-YL999, YR301-YR328	
0504	22	PA		32-9	33-51-11	D12002		4			SM00004		S		YC051-YD157	
0504	22	PA		32-9	33-51-11	D12002		4			SM00004		9		YD158-YL999, YR301-YR328	
0506	20	PA		0-7	33-51-11	D12002		5			D12002		6		YC051-YL999, YR301-YR328	
0507	20	PA		2-1	33-51-11	D12002		7			GD08004	ST..	1		YC051-YL999, YR301-YR328	
0509	16	PA		38-3	33-51-12	D12050		1			D12002		9	16	YR301-YR328	
0510	20	PA		21-8	33-51-21	D12002		10			D40086J		1		YC051-YD157	
0511	16	PA		38-3	33-51-12	D12002		11	16		D12050		1		YC051-YL999	
0513	20	PA		21-8	33-51-12	D12002		13			D40086J		5		YC051-YD157	
0513	20	PA		16-11	33-51-12	D12002		13			D12246		1		YD158-YL999	
0513	20	PA		17-6	33-51-12	D12002		13			D14824		A		YR301-YR328	
0514	16	PA		1-0	33-51-12	D12002		14	16		SM00012		9		YC051-YD157	
0514	16	PA		20-7	33-51-12	D12002		14	16		D12044		1		YD158-YL999	
0514	20	PA		12-2	33-51-12	D12002		14			D14826		A		YR301-YR328	
0515	20	PA		13-9	33-51-12	D12002		15			D12060		1		YC051-YL999	
0515	20	PA		22-6	33-51-12	D12002		15			D14830		A		YR301-YR328	

WIRE LIST

D280A108

91-21-11

Section W4140

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4142	286A4142				EMERGENCY EXIT LIGHT - RIGHT (continued)										
0516	20		PA		21-8	33-51-12	D12002	16			D40086J	2			YC051-YD157
0516	20		PA		1-0	33-51-12	D12002	16			SM00516		9		YD158-YL999, YR301-YR328
0522	20		PA		1-3	33-51-11	D12002	22			SM00009		S		YC051-YD157
0522	20		PA		1-3	33-51-11	D12002	22			SM00009		9		YD158-YL999
0522	20		PA		1-2	33-51-11	D12002	22			SM00009		9		YR301-YR328
0524	20		PA		0-7	33-51-11	D12002	20			D12002		24		YC051-YL999, YR301-YR328
0534	14		PA		20-6	33-51-12	SM00012		9		SM00028		9		YC051-YD157
0537	20		PA		6-4	33-51-12	D14826		B		GD03868	DC..	1		YR301-YR328
0538	20		PA		6-6	33-51-12	D14824		B		GD03868	DC..	1		YR301-YR328
0551	16		PA		10-1	33-51-12	D12050		2		GD03798	DC..	1		YC051-YL999
0551	16		PA		8-0	33-51-12	D12050		2		GD03794	DC..	1		YR301-YR328
0555	20		PA		8-0	33-51-12	D12060		2		GD03868	DC..	1		YC051-YL999
0555	20		PA		7-6	33-51-12	D14830		B		GD08016	DC..	1		YR301-YR328
0608	20		PA		21-4	33-51-13	D14706		A		D10714		14		YN501
0609	20		PA		4-7	33-51-13	D14706		B		GD04008	DC..	1		YN501
0610	20		PA		23-9	33-51-13	D14708		A		D10714		16		YN501
0611	16		PA		6-1	33-51-13	D14708		B		GD04008	DC..	1		YN501
0616	20		PA		3-8	33-51-13	D14724		A		SM00011		9		YN501
0617	20		PA		3-4	33-51-13	D14724		B		GD03794	DC..	1		YN501
0620	20		PA		11-2	33-51-14	D14722		A		D10744		14		YN501
0620	20		PA		22-9	33-51-14	D14706		A		D12004		13		YR301-YR328
0621	20		PA		4-8	33-51-14	D14722		B		GD03816	DC..	1		YN501
0621	20		PA		10-4	33-51-14	D14706		B		GD03806	DC..	1		YR301-YR328
0622	20		PA		25-3	33-51-14	D14714		A		D10744		15		YN501
0622	20		PA		16-8	33-51-14	D14714		A		D12004		15		YR301-YR328
0623	20		PA		8-5	33-51-14	D14714		B		GD03808	DC..	1		YN501
0623	20		PA		18-5	33-51-14	D14714		B		GD03808	DC..	1		YR301-YR328
0624	20		PA		19-10	33-51-14	D14716		A		D10744		16		YN501
0624	20		PA		17-2	33-51-14	D14708		A		D12004		14		YR301-YR328
0625	16		PA		2-5	33-51-14	D14716		B		GD03808	DC..	1		YN501
0625	20		PA		4-3	33-51-14	D14708		B		GD03806	DC..	1		YR301-YR328
0626	20		PA		18-7	33-51-14	D14832		A		D12004		16		YR301-YR328
0627	20		PA		3-4	33-51-14	D14832		B		GD08022	DC..	1		YR301-YR328
0628	20		PA		10-11	33-51-14	D14722		A		D10744		14		YR301-YR328
0629	20		PA		4-2	33-51-14	D14722		B		GD03816	DC..	1		YR301-YR328
0701	16		PA		3-6	33-51-11	D14812		1	16	GD11106	DC..	1		YN501-YR328
0702	20		PA		4-6	33-51-11	D14812		2		SM00001		9		YN501

WIRE LIST

D280A108

91-21-11

Section W4140

Page 15

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice
W4142	286A4142				EMERGENCY EXIT LIGHT - RIGHT (continued)										
0702	20		PA		4-7	33-51-11	D14812		2		SM00001		9		YR301-YR328
0703	22		PA		4-6	33-51-11	D14812		3		SM00003		9		YN501
0703	22		PA		4-7	33-51-11	D14812		3		SM00003		9		YR301-YR328
0704	22		PA		4-6	33-51-11	D14812		4		SM00004		9		YN501
0704	22		PA		4-7	33-51-11	D14812		4		SM00004		9		YR301-YR328
0706	20		PA		0-7	33-51-11	D14812		5		D14812	6			YN501-YR328
0707	20		PA		2-10	33-51-11	D14812		7		GD11106	ST..	1		YN501-YR328
0722	20		PA		4-6	33-51-11	D14812		22		SM00001		9		YN501
0722	20		PA		4-7	33-51-11	D14812		22		SM00001		9		YR301-YR328
0724	20		PA		0-7	33-51-11	D14812		20		D14812	24			YN501-YR328
1201	20		HE	DA	40-2	33-44-11	D40296J		30		D11048	1			YC051-YL999, YR301-YR328
1201	20		HE	DA	29-10	33-44-11	D40296J		30		D11048	1			YN231-YN501
1201Z				DA	0-0	33-44-11	D40296J		S/R		D11048	S/R			ALL
1202	20		HE	DB	2-3	33-44-11	D11048		2		GD03750	AC..	1		YC051-YL999, YR301-YR328
1202	20		HE	DB	1-9	33-44-11	D11048		2		GD03750	AC..	1		YN231-YN501
1202Z				DB	0-0	33-44-11	D11048		S/R		GD03750	ST..	1		ALL
1203	20		HE	DC	2-3	33-44-11	D11048		3		GD03750	ST..	1		YC051-YL999, YR301-YR328
1203	20		HE	DC	1-9	33-44-11	D11048		3		GD03750	ST..	1		YN231-YN501
1203Z				DC	0-0	33-44-11	D11048		S/R		GD03750	ST..	1		ALL
2201B	22		PB	KA	1-0	23-31-04	D40042P		2		SM00022		S		YC051-YD170
2201B	22		PB	KA	1-0	23-31-04	D40042P		2		SM00022		9		YL951-YR328
2201R	22		PB	KA	0-0	23-31-04	D40042P		1		SM00020		S		YC051-YD170
2201R	22		PB	KA	0-0	23-31-04	D40042P		1		SM00020		9		YL951-YR328
2202B	22		PB	KB	7-7	23-31-04	D40040P		2		SM00022		S		YC051-YD170
2202B	22		PB	KB	7-7	23-31-04	D40040P		2		SM00022		9		YL951-YL999, YR301-YR328
2202B	22		PB	KB	7-6	23-31-04	D40040P		2		SM00022		9		YN231-YN501
2202R	22		PB	KB	0-0	23-31-04	D40040P		1		SM00020		S		YC051-YD170
2202R	22		PB	KB	0-0	23-31-04	D40040P		1		SM00020		9		YL951-YR328
2203B	22		PB	KC	7-0	23-31-04	D40046P		2		D40007J	2			YC051-YL999, YR301-YR328
2203B	22		PB	KC	6-5	23-31-04	D40046P		2		D40007J	2			YN231-YN501
2203R	22		PB	KC	0-0	23-31-04	D40046P		1		D40007J	1			ALL
2204B	22		PB	KD	8-8	23-31-04	D40005J		2		SM00022		S		YC051-YD170
2204B	22		PB	KD	8-8	23-31-04	D40005J		2		SM00022		9		YL951-YR328
2204R	22		PB	KD	0-0	23-31-04	D40005J		1		SM00020		S		YC051-YD170

WIRE LIST

D280A108

91-21-11

Section W4140

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4142	286A4142				EMERGENCY EXIT LIGHT - RIGHT (continued)										
2204R	22	PB		KD	0-0	23-31-04	D40005J			1	SM00020		9		YL951-YR328
5501	24	PK			12-5	21-61-22	D40296J			26	D41436P		1		YN231-YN260
5501	24	PK			13-7	21-61-22	D40296J			26	D41431P		1		YN501
5502	24	PK			12-5	21-61-22	D40296J			25	D41436P		2		YN231-YN260
5502	24	PK			13-7	21-61-22	D40296J			25	D41431P		2		YN501
5503	24	PK			12-5	21-61-22	D40296J			28	D41436P		3		YN231-YN260
5503	24	PK			13-7	21-61-22	D40296J			28	D41431P		3		YN501
5504	20	PA			3-10	21-61-22	D41436P			4	GD03858	AC..	1A		YN231-YN260
5504	20	PA			4-11	21-61-22	D41431P			4	GD03858	AC..	1A		YN501
5505	20	PA			3-10	21-61-22	D41436P			5	GD03858	ST..	1A		YN231-YN260
5505	20	PA			4-11	21-61-22	D41431P			5	GD03858	ST..	1A		YN501
5506	20	PA			12-5	21-61-51	D40296J			17	D41436P		6		YN231-YN260
5506	20	PA			13-7	21-61-51	D40296J			17	D41431P		6		YN501
5507	20	PA			3-10	21-61-51	D41436P			7	GD03858	DC..	1A		YN231-YN260
5507	20	PA			4-11	21-61-51	D41431P			7	GD03858	DC..	1A		YN501
5508	20	PA			1-1	21-61-51	SM00010			9	D00094	A			YN231-YN501
5509	20	PA			27-4	21-61-51	D40296J			18	D00094	B			YN231-YN501
5510	20	PA			26-10	21-61-51	D40296J			36	SM00010		9		YN231-YN501
5511	20	PA			5-3	21-61-51	SM00010			9	GD03750	DC..	1		YN231-YN501
5512	20	PA			40-4	21-42-11	D40296J			9	SM00030		9		YC051-YL999, YR301-YR328
5512	20	PA			30-8	21-42-11	D40296J			9	SM00030		9		YN231-YN501
5513	20	PA			19-2	21-42-11	SM00030			9	SP00724		9		YC051-YL999, YR301-YR328
5513	20	PA			14-10	21-42-11	SM00030			9	SP00724		9		YN231-YN501
5514	20	PA			6-9	21-42-11	SP00726			9	GD03802	AC..	1		YC051-YL999, YR301-YR328
5514	20	PA			5-2	21-42-11	SP00726			9	GD03972	AC..	1		YN231-YN501
5515	20	PA			0-7	21-42-11	SM00030			9	SM00060		9		YC051-YL999, YR301-YR328
5515	20	PA			8-11	21-42-11	SM00030			9	SM00060		9		YN231-YN501
5516	20	PA			1-10	21-42-11	SM00062			9	GD03996	AC..	1		YC051-YL999, YR301-YR328
5516	20	PA			4-2	21-42-11	SM00062			9	GD03794	AC..	1		YN231-YN501
5526	20	PA			16-6	21-42-11	SM00030			9	D12660	= 1	VS		YC051-YL999, YR301-YR328
5526	20	PA			16-8	21-42-11	SM00030			9	D12660	= 1	VS		YN231-YN501
5527	20	PA			3-8	21-42-11	D12662			= 1	VG	GD03802	AC..	1	YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4140

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4142		286A4142			EMERGENCY EXIT LIGHT - RIGHT (continued)											
5527		20		PA		3-2	21-42-11	D12662	= 1	VG		GD03802	AC..	1		YN231-YN501
5528		20		PA		11-11	21-42-11	SM00060		9		D12652	= 1	VS		YC051-YL999, YR301-YR328
5528		20		PA		4-2	21-42-11	SM00060		9		D12652	= 1	VS		YN231-YN501
5529		20		PA		4-3	21-42-11	D12654	= 1	VG		SM00062		9		YC051-YL999, YR301-YR328
5529		20		PA		4-2	21-42-11	SM00062		9		D12654	= 1	VG		YN231-YN501
5530		20		PA		13-11	21-42-11	D12544	= 1	VS		SM00060		9		YC051-YL999, YR301-YR328
5530		20		PA		6-7	21-42-11	SM00060		9		D12544	= 1	VS		YN231-YN501
5531		20		PA		6-8	21-42-11	D12546	= 1	VG		SM00062		9		YC051-YL999, YR301-YR328
5531		20		PA		6-7	21-42-11	SM00062		9		D12546	= 1	VG		YN231-YN501
5532		20		PA		11-5	21-42-11	SM00030		9		D12656	= 1	VS		YC051-YL999, YR301-YR328
5532		20		PA		11-8	21-42-11	SM00030		9		D12656	= 1	VS		YN231-YN501
5533		20		PA		8-7	21-42-11	D12658	= 1	VG		GD03794	AC..	1		YC051-YL999, YR301-YR328
5533		20		PA		4-1	21-42-11	D12658	= 1	VG		GD03972	AC..	1		YN231-YN501
5534		20		PA		11-5	21-42-11	D12684	= 1	VS		SM00058		9		YC051-YL999, YR301-YR328
5535		20		PA		8-7	21-42-11	D12686	= 1	VG		GD03794	AC..	1		YC051-YL999, YR301-YR328
5536		20		PA		0-7	21-42-11	SM00070		9		SM00058		9		YC051-YL999, YR301-YR328
5537		20		PA		9-4	21-42-11	SM00072		9		GD03794	AC..	1		YC051-YL999, YR301-YR328
5538		20		PA		8-8	21-42-11	D12676	= 1	VS		SM00070		9		YC051-YL999, YR301-YR328
5539		20		PA		4-5	21-42-11	D12678	= 1	VG		SM00072		9		YC051-YL999, YR301-YR328
5540		20		PA		10-7	21-42-11	D12560	= 1	VS		SM00070		9		YC051-YL999, YR301-YR328
5541		20		PA		6-11	21-42-11	D12562	= 1	VG		SM00072		9		YC051-YL999, YR301-YR328
5542		20		PA		12-4	21-42-11	D12680	= 1	VS		SM00058		9		YC051-YL999
5542		20		PA		12-8	21-42-11	D12680	= 1	VS		SM00058		9		YR301-YR328
5543		20		PA		3-5	21-42-11	D12682	= 1	VG		GD08002	AC..	1		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4140

Page 18

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity			
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice	
W4142	286A4142				EMERGENCY EXIT LIGHT - RIGHT (continued)											
5544	20	PA		16-5	21-42-11	SP00708			9		SM00058		9		YC051-YL999	
5544	20	PA		16-10	21-42-11	SP00708			9		SM00058		9		YR301-YR328	
5545	20	PA		6-9	21-42-11	SP00710			9		GD08002	AC..	1		YC051-YL999, YR301-YR328	
5546	20	PA		0-7	21-42-11	SM00030			9		SM00058		9		YC051-YL999, YR301-YR328	
C-A				0-0	21-42-11	SP00724			9		M02175	= W/B			ALL	
C-B				0-0	21-42-11	SP00726			9		M02175	= WHT		ALL		
F-A				0-0	52-71-14	SP01802			9		M02221	= BLK			ALL	
F-B				0-0	52-71-14	SP01804			9		M02221	= BLK			ALL	
G-A				0-0	52-71-14	SP01814			9		S01107	= RED			ALL	
G-B				0-0	52-71-14	SP01816			9		S01107	= WHT		ALL		
H-A				0-0	52-71-14	SP01806			9		S01114	= WHT		ALL		
H-B				0-0	52-71-14	SP01808			9		S01114	= WHT		ALL		
I-A				0-0	52-71-14	SP01810			9		S01106	= RED			ALL	
I-B				0-0	52-71-14	SP01812			9		S01106	= WHT		ALL		
J-A				0-0	21-42-11	SP00708			9		M02179	= W/B			YC051-YL999, YR301-YR328	
J-B				0-0	21-42-11	SP00710			9		M02179	= WHT		YC051-~ YL999, YR301-~ YR328		
N-A				0-0	52-71-14	SP01818			9		M02222	= BLK			YC051-YL999, YR301-YR328	
N-B				0-0	52-71-14	SP01820			9		M02222	= BLK			YC051-YL999, YR301-YR328	
P-A				0-0	52-71-14	SP01826			9		S01110	= RED			YC051-YL999, YR301-YR328	
P-B				0-0	52-71-14	SP01828			9		S01110	= WHT		YC051-~ YL999, YR301-~ YR328		
Q-A				0-0	52-71-14	SP01830			9		S01111	= RED			YC051-YL999, YR301-YR328	

WIRE LIST
D280A108

91-21-11
Section W4140
Page 19
Nov 12/2012

Bundle No.	Part Number			Description	Diagram			From			To			Effectivity	
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type
W4142	286A4142			EMERGENCY EXIT LIGHT - RIGHT (continued)											
Q-B					0-0	52-71-14	SP01832			9		S01111	= WHT		YC051-~ YL999, YR301-~ YR328
R-A					0-0	52-71-14	SP01822			9		S01115	= WHT		YC051-~ YL999, YR301-~ YR328
R-B					0-0	52-71-14	SP01824			9		S01115	= WHT		YC051-~ YL999, YR301-~ YR328
W4146	286A4146			FLUORESCENT LIGHTING - RIGHT CEILING											
0001	18		PA		4-11	33-22-31	D40018P			1		SM00001		S	YC051-YL999
0001	18		PA		6-8	33-22-31	D40018P			1		SM00001		S	YN231-YN260
0002	18		PA		7-2	33-22-31	D40018P			2		GD03854	AC..	1	YC051-YN260
0003	18		PA		7-2	33-22-31	D40018P			3		GD03854	ST..	1	YC051-YN260
0005	24		PK		4-11	33-22-31	D40018P			5		SM00005		S	YC051-YL999
0005	24		PK		6-8	33-22-31	D40018P			5		SM00005		S	YN231-YN260
0006	24		PK		4-11	33-22-31	D40018P			6		SM00006		S	YC051-YL999
0006	24		PK		6-8	33-22-31	D40018P			6		SM00006		S	YN231-YN260
0007	20		PA		6-3	33-26-31	D40018P			7		D40184J		3	YC051-YL999
0007	20		PA		6-2	33-26-31	D40018P			7		D40184J		3	YN231-YN260
0008	18		PA		4-3	33-26-31	D40018P			8		GD11108	AC..	1	YC051-YN260
0009	20		PA		6-3	33-26-31	D40018P			9		D40184J		1	YC051-YL999
0009	20		PA		6-2	33-26-31	D40018P			9		D40184J		1	YN231-YN260
0011	18		PA		6-6	33-22-31	D11882			1		SM00001		S	YC051-YL999
0011	18		PA		4-6	33-22-31	D11882			1		SM00001		S	YN231-YN260
0012	18		PA		4-5	33-22-31	D11882			2		GD08058	AC..	1	YC051-YL999
0012	18		PA		4-2	33-22-31	D11882			2		GD08058	AC..	1	YN231-YN260
0013	18		PA		4-5	33-22-31	D11882			3		GD08058	ST..	1	YC051-YL999
0013	18		PA		4-2	33-22-31	D11882			3		GD08058	ST..	1	YN231-YN260
0015	24		PK		6-6	33-22-31	D11882			5		SM00005		S	YC051-YL999
0015	24		PK		4-6	33-22-31	D11882			5		SM00005		S	YN231-YN260
0016	24		PK		6-6	33-22-31	D11882			6		SM00006		S	YC051-YL999
0016	24		PK		4-6	33-22-31	D11882			6		SM00006		S	YN231-YN260
0021	18		PA		7-6	33-22-31	D11884			1		SM00021		S	YC051-YL999
0021	18		PA		9-5	33-22-31	D11884			1		SM00001		S	YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W4140

Page 20

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4146	286A4146			FLUORESCENT LIGHTING - RIGHT CEILING (continued)											
0022	18		PA		4-3	33-22-31	D11884		2		GD03846	AC..	1		YC051-YL999
0022	18		PA		3-10	33-22-31	D11884		2		GD03846	AC..	1		YN231-YN260
0023	18		PA		4-3	33-22-31	D11884		3		GD03846	ST..	1		YC051-YL999
0023	18		PA		3-10	33-22-31	D11884		3		GD03846	ST..	1		YN231-YN260
0025	24		PK		7-6	33-22-31	D11884		5		SM00025		S		YC051-YL999
0025	24		PK		6-5	33-22-31	D11884		5		SM00025		S		YN231-YN260
0026	24		PK		7-6	33-22-31	D11884		6		SM00026		S		YC051-YL999
0026	24		PK		6-5	33-22-31	D11884		6		SM00026		S		YN231-YN260
0031	18		PA		4-6	33-22-31	D11952		1		SM00021		S		YC051-YL999
0031	18		PA		13-4	33-22-31	D11886		1		SM00041		S		YN231-YN260
0032	18		PA		3-9	33-22-31	D11952		2		GD03868	AC..	1		YC051-YL999
0032	18		PA		6-6	33-22-31	D11886		2		GD03868	AC..	1		YN231-YN260
0033	18		PA		3-9	33-22-31	D11952		3		GD03868	ST..	1		YC051-YL999
0033	18		PA		6-6	33-22-31	D11886		3		GD03868	ST..	1		YN231-YN260
0034	24		PK		4-6	33-22-31	D11952		4		SM00024		S		YD158-YL999
0034	24		PK		13-4	33-22-31	D11886		4		SM00044		S		YN231-YN260
0035	24		PK		4-6	33-22-31	D11952		5		SM00025		S		YC051-YL999
0035	24		PK		6-7	33-22-31	D11886		5		SM00025		S		YN231-YN260
0036	24		PK		4-6	33-22-31	D11952		6		SM00026		S		YC051-YL999
0036	24		PK		6-7	33-22-31	D11886		6		SM00026		S		YN231-YN260
0041	18		PA		6-5	33-22-31	D11958		1		SM00041		S		YC051-YL999
0041	18		PA		7-5	33-22-31	D11888		1		SM00041		S		YN231-YN260
0042	18		PA		8-5	33-22-31	D11958		2		GD03798	AC..	1		YC051-YL999
0042	18		PA		9-2	33-22-31	D11888		2		GD03872	AC..	1		YN231-YN260
0043	18		PA		8-5	33-22-31	D11958		3		GD03798	ST..	1		YC051-YL999
0043	18		PA		9-2	33-22-31	D11888		3		GD03872	ST..	1		YN231-YN260
0044	24		PK		6-5	33-22-31	D11958		4		SM00044		S		YD158-YL999
0045	24		PK		6-5	33-22-31	D11958		5		SM00045		S		YC051-YL999
0045	24		PK		7-5	33-22-31	D11888		5		SM00045		S		YN231-YN260
0046	24		PK		6-5	33-22-31	D11958		6		SM00046		S		YC051-YL999
0046	24		PK		7-5	33-22-31	D11888		6		SM00046		S		YN231-YN260
0051	18		PA		9-5	33-22-32	D11960		1		SM00061		S		YC051-YL999
0051	18		PA		7-3	33-22-32	D11890		1		SM00061		S		YN231-YN260
0052	18		PA		6-9	33-22-32	D11960		2		GD03804	AC..	1		YC051-YL999
0052	18		PA		3-9	33-22-32	D11890		2		GD04010	AC..	1		YN231-YN260
0053	18		PA		6-9	33-22-32	D11960		3		GD03804	ST..	1		YC051-YL999
0053	18		PA		3-9	33-22-32	D11890		3		GD04010	ST..	1		YN231-YN260
0055	24		PK		9-5	33-22-32	D11960		5		SM00065		S		YC051-YL999
0055	24		PK		7-3	33-22-32	D11890		5		SM00065		S		YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W4140

Page 21

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W4146	286A4146				FLUORESCENT LIGHTING - RIGHT CEILING (continued)											
0056	24		PK		9-5	33-22-32		D11960				SM00066		S		YC051-YL999
0056	24		PK		7-3	33-22-32		D11890				SM00066		S		YN231-YN260
0061	18		PA		4-1	33-22-32		D11962				SM00061		S		YC051-YL999
0061	18		PA		7-0	33-22-32		D11892				SM00061		S		YN231-YN260
0062	18		PA		5-1	33-22-32		D11962				GD03806	AC..	1		YC051-YL999
0062	18		PA		6-8	33-22-32		D11892				GD04008	AC..	1		YN231-YN260
0063	18		PA		5-1	33-22-32		D11962				GD03806	ST..	1		YC051-YL999
0063	18		PA		6-8	33-22-32		D11892				GD04008	ST..	1		YN231-YN260
0064	24		PK		7-0	33-22-32		D11892				SM00064		S		YN231-YN260
0065	24		PK		4-1	33-22-32		D11962				SM00065		S		YC051-YL999
0065	24		PK		7-0	33-22-32		D11892				SM00065		S		YN231-YN260
0066	24		PK		4-1	33-22-32		D11962				SM00066		S		YC051-YL999
0066	24		PK		7-0	33-22-32		D11892				SM00066		S		YN231-YN260
0071	18		PA		6-5	33-22-32		D11966				SM00081		S		YC051-YD157, YL951-YL999
0071	18		PA		11-8	33-22-32		D11966				SM00071		S		YD158-YD170
0071	18		PA		14-8	33-22-32		D11894				SM00081		S		YN231-YN260
0072	18		PA		6-5	33-22-32		D11966				GD08026	AC..	1		YC051-YL999
0072	18		PA		7-11	33-22-32		D11894				GD03806	AC..	1		YN231-YN260
0073	18		PA		6-5	33-22-32		D11966				GD08026	ST..	1		YC051-YL999
0073	18		PA		7-11	33-22-32		D11894				GD03806	ST..	1		YN231-YN260
0074	24		PK		34-4	33-22-32		D11966				SM00044		S		YC051-YD157
0075	24		PK		6-5	33-22-32		D11966				SM00085		S		YC051-YD157, YL951-YL999
0075	24		PK		11-8	33-22-32		D11966				SM00075		S		YD158-YD170
0075	24		PK		14-8	33-22-32		D11894				SM00085		S		YN231-YN260
0076	24		PK		6-5	33-22-32		D11966				SM00086		S		YC051-YD157, YL951-YL999
0076	24		PK		11-8	33-22-32		D11966				SM00076		S		YD158-YD170
0076	24		PK		14-8	33-22-32		D11894				SM00086		S		YN231-YN260
0081	18		PA		6-8	33-22-32		D11968				SM00081		S		YC051-YL999
0081	18		PA		7-9	33-22-32		D11896				SM00081		S		YN231-YN260
0082	18		PA		4-10	33-22-32		D11968				GD03808	AC..	1		YC051-YL999
0082	18		PA		5-3	33-22-32		D11896				GD03808	AC..	1		YN231-YN260
0083	18		PA		4-10	33-22-32		D11968				GD03808	ST..	1		YC051-YL999
0083	18		PA		5-3	33-22-32		D11896				GD03808	ST..	1		YN231-YN260
0085	24		PK		6-8	33-22-32		D11968				SM00085		S		YC051-YL999
0085	24		PK		7-9	33-22-32		D11896				SM00085		S		YN231-YN260
0086	24		PK		6-8	33-22-32		D11968				SM00086		S		YC051-YL999

WIRE LIST

D280A108

91-21-11

Section W4140

Page 22

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W4146	286A4146				FLUORESCENT LIGHTING - RIGHT CEILING (continued)												
0086	24		PK		7-9	33-22-32	D11896		6			SM00086		S		YN231-YN260	
0091	18		PA		12-4	33-22-32	D11898		1			SM00081		S		YC051-YL999	
0091	18		PA		3-5	33-22-32	D11898		1			SM00081		S		YN231-YN260	
0092	18		PA		5-5	33-22-32	D11898		2			GD04002	AC..	1		YC051-YL999	
0092	18		PA		6-1	33-22-32	D11898		2			GD04002	AC..	1		YN231-YN260	
0093	18		PA		5-5	33-22-32	D11898		3			GD04002	ST..	1		YC051-YL999	
0093	18		PA		6-1	33-22-32	D11898		3			GD04002	ST..	1		YN231-YN260	
0094	24		PK		23-1	33-22-32	D11898		4			SM00074		S		YD158-YL999	
0094	24		PK		24-2	33-22-32	D11898		4			SM00064		S		YN231-YN260	
0095	24		PK		12-4	33-22-32	D11898		5			SM00085		S		YC051-YL999	
0095	24		PK		3-5	33-22-32	D11898		5			SM00085		S		YN231-YN260	
0096	24		PK		12-4	33-22-32	D11898		6			SM00086		S		YC051-YL999	
0096	24		PK		3-5	33-22-32	D11898		6			SM00086		S		YN231-YN260	
0131	18		PA		11-8	33-22-31	D11954		1			SM00021		S		YC051-YD157, YL951-YL999	
0131	18		PA		13-8	33-22-31	D11954		1			SM00041		S		YD158-YD170	
0132	18		PA		3-6	33-22-31	D11954		2			GD08014	AC..	1		YC051-YL999	
0133	18		PA		3-6	33-22-31	D11954		3			GD08014	ST..	1		YC051-YL999	
0135	24		PK		6-10	33-22-31	D11954		5			SM00035		S		YC051-YD157, YL951-YL999	
0135	24		PK		13-8	33-22-31	D11954		5			SM00045		S		YD158-YD170	
0136	24		PK		6-10	33-22-31	D11954		6			SM00036		S		YC051-YD157, YL951-YL999	
0136	24		PK		13-8	33-22-31	D11954		6			SM00046		S		YD158-YD170	
0141	18		PA		8-3	33-22-31	D11956		1			SM00041		S		YC051-YL999	
0142	18		PA		3-9	33-22-31	D11956		2			GD08018	AC..	1		YC051-YL999	
0143	18		PA		3-9	33-22-31	D11956		3			GD08018	ST..	1		YC051-YL999	
0144	24		PK		8-3	33-22-31	D11956		4			SM00044		S		YC051-YD157	
0145	24		PK		8-3	33-22-31	D11956		5			SM00045		S		YC051-YL999	
0146	24		PK		8-3	33-22-31	D11956		6			SM00046		S		YC051-YL999	
0171	18		PA		10-11	33-22-32	D11964		1			SM00061		S		YC051-YD157, YL951-YL999	
0171	18		PA		3-7	33-22-32	D11964		1			SM00071		S		YD158-YD170	
0172	18		PA		6-1	33-22-32	D11964		2			GD08022	AC..	1		YC051-YL999	
0173	18		PA		6-1	33-22-32	D11964		3			GD08022	ST..	1		YC051-YL999	
0174	24		PK		3-7	33-22-32	D11964		4			SM00074		S		YD158-YL999	
0175	24		PK		3-7	33-22-32	D11964		5			SM00075		S		YC051-YL999	
0176	24		PK		3-7	33-22-32	D11964		6			SM00076		S		YC051-YL999	
0210	20		PA		6-0	33-51-12	D40018P		10			D07184P	= 1	VR		YD158-YL999	

WIRE LIST

D280A108

91-21-11

Section W4140

Page 23

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4146		286A4146			FLUORESCENT LIGHTING - RIGHT CEILING (continued)											
0210		20		PA		6-3	33-51-12	D40018P	10			D07184P	= 1	VR		YN231-YN260
0211		20		PA		7-2	33-51-12	D40018P	11			GD03854	DC..	1		YD158-YN260
0301		18		PA		8-1	33-22-31	D42002J	1			SM00001		S		YC051-YL999
0301		18		PA		6-8	33-22-31	D42002J	1			SM00001		S		YN231-YN260
0321		18		PA		13-0	33-22-31	SM00001		S		SM00021		S		YC051-YL999
0341		18		PA		15-3	33-22-31	D42004J	1			SM00041		S		YC051-YD157, YL951-YL999
0341		18		PA		10-3	33-22-31	D40990J	1			SM00041		S		YD158-YD170
0341		18		PA		10-9	33-22-31	D42004J	1			SM00041		S		YN231-YN260
0361		18		PA		16-11	33-22-32	SM00041		S		SM00061		S		YC051-YD157, YL951-YL999
0361		18		PA		3-6	33-22-32	D42004J	1			SM00061		S		YD158-YD170
0361		18		PA		8-5	33-22-32	SM00041		S		SM00061		S		YN231-YN260
0363		18		PA		24-5	SPARE	D40990J	2			D42004J	3			YD158-YD170
0371		18		PA		7-10	33-22-32	SM00061		S		SM00071		S		YD158-YD170
0381		18		PA		12-9	33-22-32	D42006J	1			SM00081		S		YC051-YD157, YL951-YL999
0381		18		PA		2-8	33-22-32	D40996J	1			SM00081		S		YD158-YD170
0381		18		PA		4-3	33-22-32	D42006J	1			SM00081		S		YN231-YN260
0403		24		PK		36-10	33-22-31	D42008J	3			SM00044		S		YC051-YD157
0403		24		PK		18-11	33-22-31	D42008J	3			SM00024		S		YD158-YL999
0405		24		PK		7-0	33-22-31	D42008J	5			SM00005		S		YC051-YL999
0405		24		PK		8-3	33-22-31	D42008J	5			SM00005		S		YN231-YN260
0406		24		PK		7-0	33-22-31	D42008J	6			SM00006		S		YC051-YL999
0406		24		PK		8-3	33-22-31	D42008J	6			SM00006		S		YN231-YN260
0425		24		PK		13-0	33-22-31	SM00005		S		SM00025		S		YC051-YL999
0425		24		PK		10-11	33-22-31	SM00005		S		SM00025		S		YN231-YN260
0426		24		PK		13-0	33-22-31	SM00006		S		SM00026		S		YC051-YL999
0426		24		PK		10-11	33-22-31	SM00006		S		SM00026		S		YN231-YN260
0435		24		PK		12-1	33-22-31	SM00025		S		SM00035		S		YC051-YD157, YL951-YL999
0436		24		PK		12-1	33-22-31	SM00026		S		SM00036		S		YC051-YD157, YL951-YL999
0444		24		PK		18-11	33-22-31	SM00024		S		SM00044		S		YD158-YL999
0444		24		PK		31-4	33-22-31	D42008J	3			SM00044		S		YN231-YN260
0445		24		PK		7-11	33-22-31	SM00035		S		SM00045		S		YC051-YD157, YL951-YL999
0445		24		PK		18-11	33-22-31	SM00025		S		SM00045		S		YD158-YD170
0445		24		PK		14-3	33-22-31	SM00025		S		SM00045		S		YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W4140

Page 24

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				Effectivity
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W4146	286A4146			FLUORESCENT LIGHTING - RIGHT CEILING (continued)											
0446	24		PK		7-11	33-22-31	SM00036			S	SM00046			S	YC051-YD157, YL951-YL999
0446	24		PK		18-11	33-22-31	SM00026			S	SM00046			S	YD158-YD170
0446	24		PK		14-3	33-22-31	SM00026			S	SM00046			S	YN231-YN260
0464	24		PK		8-5	33-22-32	SM00044			S	SM00064			S	YN231-YN260
0465	24		PK		16-11	33-22-32	SM00045			S	SM00065			S	YC051-YL999
0465	24		PK		8-5	33-22-32	SM00045			S	SM00065			S	YN231-YN260
0466	24		PK		16-11	33-22-32	SM00046			S	SM00066			S	YC051-YL999
0466	24		PK		8-5	33-22-32	SM00046			S	SM00066			S	YN231-YN260
0474	24		PK		23-8	33-22-32	SM00044			S	SM00074			S	YD158-YL999
0475	24		PK		7-10	33-22-32	SM00065			S	SM00075			S	YC051-YL999
0476	24		PK		7-10	33-22-32	SM00066			S	SM00076			S	YC051-YL999
0485	24		PK		11-10	33-22-32	SM00075			S	SM00085			S	YC051-YL999
0485	24		PK		21-3	33-22-32	SM00065			S	SM00085			S	YN231-YN260
0486	24		PK		11-10	33-22-32	SM00076			S	SM00086			S	YC051-YL999
0486	24		PK		21-3	33-22-32	SM00066			S	SM00086			S	YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W4140

Page 25 End

Nov 12/2012



WIRE LIST

91-21-11

Section W4160

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4162	286A4162			NS/FSB SIGN-VIDEO PANEL, FORWARD-RIGHT (continued)											
3405B	20	PC	E2		12-10	33-25-61	SM00032		S		D10427	2			YC051-YD157
3405R	20	PC	E2		0-0	33-25-61	SM00031		S		D10427	1			YC051-YD157
3405Y	20	PC	E2		0-0	33-25-61	SM00033		S		D10427	3			YC051-YD157
3431B	20	PC	F3		2-9	33-25-61	D40862J	2			SM00002		S		YC051-YD157
3431R	20	PC	F3		0-0	33-25-61	D40862J	1			SM00001		S		YC051-YD157
3431Y	20	PC	F3		0-0	33-25-61	D40862J	3			SM00003		S		YC051-YD157
3432B	20	PC	G3		2-2	33-25-61	SM00002		S		SM00012		S		YC051-YD157
3432R	20	PC	G3		0-0	33-25-61	SM00001		S		SM00011		S		YC051-YD157
3432Y	20	PC	G3		0-0	33-25-61	SM00003		S		SM00013		S		YC051-YD157
3433B	20	PC	H3		8-7	33-25-61	SM00012		S		SM00022		S		YC051-YD157
3433R	20	PC	H3		0-0	33-25-61	SM00011		S		SM00021		S		YC051-YD157
3433Y	20	PC	H3		0-0	33-25-61	SM00013		S		SM00023		S		YC051-YD157
3434B	20	PC	I3		8-4	33-25-61	SM00022		S		SM00032		S		YC051-YD157
3434R	20	PC	I3		0-0	33-25-61	SM00021		S		SM00031		S		YC051-YD157
3434Y	20	PC	I3		0-0	33-25-61	SM00023		S		SM00033		S		YC051-YD157
3502B	20	PC	B8		6-9	33-25-61	SM00206		S		SM00512		S		YD158-YD170
3502R	20	PC	B8		0-0	33-25-61	SM00106		S		SM00502		S		YD158-YD170
3502Y	20	PC	B8		0-0	33-25-61	SM00306		S		SM00522		S		YD158-YD170
3506B	20	PC	F8		8-4	33-25-61	SM00512		S		SM00516		S		YD158-YD170
3506R	20	PC	F8		0-0	33-25-61	SM00502		S		SM00506		S		YD158-YD170
3506Y	20	PC	F8		0-0	33-25-61	SM00522		S		SM00526		S		YD158-YD170
3512B	20	PC	L8		4-8	33-25-61	D10391	2			SM00512		S		YD158-YD170
3512R	20	PC	L8		0-0	33-25-61	D10391	1			SM00502		S		YD158-YD170
3512Y	20	PC	L8		0-0	33-25-61	D10391	3			SM00522		S		YD158-YD170
3516B	20	PC	P8		4-8	33-25-61	D10415	2			SM00516		S		YD158-YD170
3516R	20	PC	P8		0-0	33-25-61	D10415	1			SM00506		S		YD158-YD170
3516Y	20	PC	P8		0-0	33-25-61	D10415	3			SM00526		S		YD158-YD170
3604B	20	PC	D4		2-2	33-25-61	D40862J	2			SM00204		S		YD158-YD170
3604B	18	PC	D4		10-4	33-25-61	D40862J	2			SM00612		S		YN501
3604B	18	PC	D4		10-7	33-25-61	D40862J	2			SM00612		S		YR301-YR328
3604R	20	PC	D4		0-0	33-25-61	D40862J	1			SM00104		S		YD158-YD170
3604R	18	PC	D4		0-0	33-25-61	D40862J	1			SM00602		S		YN501-YR328
3604Y	20	PC	D4		0-0	33-25-61	D40862J	3			SM00304		S		YD158-YD170
3604Y	18	PC	D4		0-0	33-25-61	D40862J	3			SM00622		S		YN501-YR328
3606B	20	PC	F4		1-0	33-25-61	SM00204		S		SM00206		S		YD158-YD170
3606R	20	PC	F4		0-0	33-25-61	SM00104		S		SM00106		S		YD158-YD170
3606Y	20	PC	F4		0-0	33-25-61	SM00304		S		SM00306		S		YD158-YD170

WIRE LIST

D280A108

91-21-11
Section W4160
Page 2
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To			Effectivity					
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type		Splice	Equip	Term	Type	Splice
I	W4164	286A4164			NS/FSB SIGN-VIDEO PANEL, AFT-RIGHT											
	3206B	20	PC	YF		8-2	33-25-61	D10463		2		SM00206		S		YD158-YD170
	3206R	20	PC	YF		0-0	33-25-61	D10463		1		SM00106		S		YD158-YD170
	3206Y	20	PC	YF		0-0	33-25-61	D10463		3		SM00306		S		YD158-YD170
	3210B	20	PC	YJ		5-4	33-25-61	D10487		2		SM00210		S		YD158-YD170
	3210R	20	PC	YJ		0-0	33-25-61	D10487		1		SM00110		S		YD158-YD170
	3210Y	20	PC	YJ		0-0	33-25-61	D10487		3		SM00310		S		YD158-YD170
	3212B	20	PC	YL		7-1	33-25-61	D10523		2		SM00212		S		YD158-YD170
	3212R	20	PC	YL		0-0	33-25-61	D10523		1		SM00112		S		YD158-YD170
	3212Y	20	PC	YL		0-0	33-25-61	D10523		3		SM00312		S		YD158-YD170
	3214B	20	PC	YN		11-3	33-25-61	D10983		2		SM00212		S		YD158-YD170
	3214R	20	PC	YN		0-0	33-25-61	D10983		1		SM00112		S		YD158-YD170
	3214Y	20	PC	YN		0-0	33-25-61	D10983		3		SM00312		S		YD158-YD170
I	3401B	20	PC	A2		7-7	33-25-61	SM00002			S	D10439	2			YC051-YD157
I	3401R	20	PC	A2		0-0	33-25-61	SM00001			S	D10439	1			YC051-YD157
I	3401Y	20	PC	A2		0-0	33-25-61	SM00003			S	D10439	3			YC051-YD157
I	3402B	20	PC	B2		4-8	33-25-61	SM00012			S	D10463	2			YC051-YD157
I	3402R	20	PC	B2		0-0	33-25-61	SM00011			S	D10463	1			YC051-YD157
I	3402Y	20	PC	B2		0-0	33-25-61	SM00013			S	D10463	3			YC051-YD157
I	3403B	20	PC	C2		4-10	33-25-61	SM00022			S	D10475	2			YC051-YD157
I	3403R	20	PC	C2		0-0	33-25-61	SM00021			S	D10475	1			YC051-YD157
I	3403Y	20	PC	C2		0-0	33-25-61	SM00023			S	D10475	3			YC051-YD157
I	3404B	20	PC	D2		4-4	33-25-61	SM00032			S	D10499	2			YC051-YD157
I	3404R	20	PC	D2		0-0	33-25-61	SM00031			S	D10499	1			YC051-YD157
I	3404Y	20	PC	D2		0-0	33-25-61	SM00033			S	D10499	3			YC051-YD157
I	3405B	20	PC	E2		4-8	33-25-61	SM00042			S	D10511	2			YC051-YD157
I	3405R	20	PC	E2		0-0	33-25-61	SM00041			S	D10511	1			YC051-YD157
I	3405Y	20	PC	E2		0-0	33-25-61	SM00043			S	D10511	3			YC051-YD157
I	3406B	20	PC	F2		11-10	33-25-61	SM00042			S	D10523	2			YC051-YD157
I	3406R	20	PC	F2		0-0	33-25-61	SM00041			S	D10523	1			YC051-YD157
I	3406Y	20	PC	F2		0-0	33-25-61	SM00043			S	D10523	3			YC051-YD157
I	3431B	20	PC	F3		2-6	33-25-61	D40864J	2			SM00002		S		YC051-YD157
I	3431R	20	PC	F3		0-0	33-25-61	D40864J	1			SM00001		S		YC051-YD157
I	3431Y	20	PC	F3		0-0	33-25-61	D40864J	3			SM00003		S		YC051-YD157
I	3432B	20	PC	G3		6-3	33-25-61	SM00002			S	SM00012		S		YC051-YD157
I	3432R	20	PC	G3		0-0	33-25-61	SM00001			S	SM00011		S		YC051-YD157
I	3432Y	20	PC	G3		0-0	33-25-61	SM00003			S	SM00013		S		YC051-YD157
I	3433B	20	PC	H3		8-1	33-25-61	SM00012			S	SM00022		S		YC051-YD157
I	3433R	20	PC	H3		0-0	33-25-61	SM00011			S	SM00021		S		YC051-YD157
I	3433Y	20	PC	H3		0-0	33-25-61	SM00013			S	SM00023		S		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W4160

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4164	286A4164				NS/FSB SIGN-VIDEO PANEL, AFT-RIGHT (continued)										
3434B	20	PC	I3		8-6	33-25-61	SM00022		S		SM00032		S		YC051-YD157
3434R	20	PC	I3		0-0	33-25-61	SM00021		S		SM00031		S		YC051-YD157
3434Y	20	PC	I3		0-0	33-25-61	SM00023		S		SM00033		S		YC051-YD157
3435B	20	PC	J3		7-9	33-25-61	SM00032		S		SM00042		S		YC051-YD157
3435R	20	PC	J3		0-0	33-25-61	SM00031		S		SM00041		S		YC051-YD157
3435Y	20	PC	J3		0-0	33-25-61	SM00033		S		SM00043		S		YC051-YD157
3606B	20	PC	F4		2-4	33-25-61	D40864J	2			SM00206		S		YD158-YD170
3606R	20	PC	F4		0-0	33-25-61	D40864J	1			SM00106		S		YD158-YD170
3606Y	20	PC	F4		0-0	33-25-61	D40864J	3			SM00306		S		YD158-YD170
3610B	20	PC	J4		7-1	33-25-61	SM00206		S		SM00210		S		YD158-YD170
3610R	20	PC	J4		0-0	33-25-61	SM00106		S		SM00110		S		YD158-YD170
3610Y	20	PC	J4		0-0	33-25-61	SM00306		S		SM00310		S		YD158-YD170
3612B	20	PC	L4		11-11	33-25-61	SM00212		S		SM00712		S		YD158-YD170
3612R	20	PC	L4		0-0	33-25-61	SM00112		S		SM00702		S		YD158-YD170
3612Y	20	PC	L4		0-0	33-25-61	SM00312		S		SM00722		S		YD158-YD170
3702B	20	PC	B8		3-10	33-25-61	SM00210		S		SM00712		S		YD158-YD170
3702R	20	PC	B8		0-0	33-25-61	SM00110		S		SM00702		S		YD158-YD170
3702Y	20	PC	B8		0-0	33-25-61	SM00310		S		SM00722		S		YD158-YD170
3712B	20	PC	L8		6-0	33-25-61	D10499	2			SM00712		S		YD158-YD170
3712R	20	PC	L8		0-0	33-25-61	D10499	1			SM00702		S		YD158-YD170
3712Y	20	PC	L8		0-0	33-25-61	D10499	3			SM00722		S		YD158-YD170
W4166	286A4166				LED LIGHTING - CEILING/WASH RIGHT										
0001	18	PA			4-6	33-22-51	D14574	B			SM00001		S		YN501
0002	18	PA			6-6	33-22-51	D14574	C			GD03868	AC..	1		YN501
0003	18	PA			6-6	33-22-51	D14574	A			GD03868	ST..	1		YN501
0011	18	PA			3-11	33-22-51	D14570	B			SM00002		S		YN501
0012	18	PA			6-6	33-22-51	D14570	C			GD03872	AC..	1		YN501
0013	18	PA			6-6	33-22-51	D14570	A			GD03872	ST..	1		YN501
0014	18	PA			16-0	33-22-51	D41066J	B			SM00001		S		YN501
0014	18	PA			8-2	33-22-51	D41066J	B			SM00019		S		YR301-YR328
0015	18	PA			6-1	33-22-51	SM00001		S		SM00002		S		YN501
0016	18	PA			11-2	33-22-51	SM00003		S		SM00002		S		YN501
0017	18	PA			19-0	33-22-51	D41084J	B			SM00004		S		YN501
0017	18	PA			26-4	33-22-51	D41084J	B			SM00010		S		YR301-YR314, YR317-YR318, YR320-YR328
0017	18	PA			26-4	33-22-51	D41084J	B			SM00009		S		YR315-YR316, YR319
0019	18	PA			9-10	33-22-51	SM00001		S		SM00005		S		YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4160

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4166	286A4166				LED LIGHTING - CEILING/WASH RIGHT (continued)										
0020	18		PA		6-6	33-22-51	SM00005		S		SM00006		S		YR301-YR328
0028	18		PA		21-3	33-22-51	SM00018		S		SM00007		S		YR301-YR314, YR317-YR318, YR320-YR328
0029	18		PA		4-0	33-22-51	SM00008		S		SM00009		S		YR315-YR316, YR319
0030	18		PA		4-0	33-22-51	SM00018		S		SM00010		S		YR301-YR314, YR317-YR318, YR320-YR328
0031	18		PA		9-4	33-22-51	SM00001		S		SM00019		S		YR301-YR328
0034	18		PA		9-0	33-22-51	D15012		B		SM00001		S		YR301-YR328
0035	18		PA		6-6	33-22-51	D15012		C		GD08014	AC..	1		YR301-YR328
0036	18		PA		6-6	33-22-51	D15012		A		GD08014	ST..	1		YR301-YR328
0044	18		PA		5-0	33-22-51	D15010		B		SM00005		S		YR301-YR328
0045	18		PA		6-6	33-22-51	D15010		C		GD08018	AC..	1		YR301-YR328
0046	18		PA		6-6	33-22-51	D15010		A		GD08018	ST..	1		YR301-YR328
0054	18		PA		9-11	33-22-51	D15008		B		SM00005		S		YR301-YR328
0055	18		PA		6-6	33-22-51	D15008		C		GD03750	AC..	1		YR301-YR328
0056	18		PA		6-6	33-22-51	D15008		A		GD03750	ST..	1		YR301-YR328
0061	18		PA		3-11	33-22-51	D14566		B		SM00002		S		YN501
0062	18		PA		6-6	33-22-51	D14566		C		GD03750	AC..	1		YN501
0063	18		PA		6-6	33-22-51	D14566		A		GD03750	ST..	1		YN501
0064	18		PA		9-10	33-22-51	D15006		B		SM00006		S		YR301-YR328
0065	18		PA		6-6	33-22-51	D15006		C		GD03798	AC..	1		YR301-YR328
0066	18		PA		6-6	33-22-51	D15006		A		GD03798	ST..	1		YR301-YR328
0071	18		PA		4-5	33-22-51	D14562		B		SM00003		S		YN501
0072	18		PA		6-6	33-22-51	D14562		C		GD03798	AC..	1		YN501
0073	18		PA		6-6	33-22-51	D14562		A		GD03798	ST..	1		YN501
0074	18		PA		15-0	33-22-51	D15004		B		SM00006		S		YR301-YR328
0075	18		PA		6-6	33-22-51	D15004		C		GD03804	AC..	1		YR301-YR328
0076	18		PA		6-6	33-22-51	D15004		A		GD03804	ST..	1		YR301-YR328
0081	18		PA		4-1	33-22-51	D14558		B		SM00003		S		YN501
0082	18		PA		6-6	33-22-51	D14558		C		GD04010	AC..	1		YN501
0083	18		PA		6-6	33-22-51	D14558		A		GD04010	ST..	1		YN501
0084	18		PA		24-6	33-22-51	D15410		B		SM00008		S		YR315-YR316, YR319
0085	18		PA		6-6	33-22-51	D15410		C		GD04008	AC..	1		YR315-YR316, YR319
0086	18		PA		6-6	33-22-51	D15410		A		GD04008	ST..	1		YR315-YR316, YR319
0111	18		PA		9-7	33-22-51	D15364		B		SM00003		S		YN501
0112	18		PA		6-6	33-22-51	D15364		C		GD03806	AC..	1		YN501
0113	18		PA		6-6	33-22-51	D15364		A		GD03806	ST..	1		YN501

WIRE LIST

D280A108

91-21-11

Section W4160

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4166	286A4166				LED LIGHTING - CEILING/WASH RIGHT (continued)											
0114	18		PA		3-5	33-22-51		D14760		B		SM00001		S		YR301-YR328
0115	18		PA		6-6	33-22-51		D14760		C		GD03868	AC..	1		YR301-YR328
0116	18		PA		6-6	33-22-51		D14760		A		GD03868	ST..	1		YR301-YR328
0121	18		PA		11-7	33-22-51		D15362		B		SM00004		S		YN501
0122	18		PA		6-6	33-22-51		D15362		C		GD08068	AC..	1		YN501
0123	18		PA		6-6	33-22-51		D15362		A		GD08068	ST..	1		YN501
0131	18		PA		6-6	33-22-51		D15360		B		SM00004		S		YN501
0132	18		PA		6-6	33-22-51		D15360		C		GD03808	AC..	1		YN501
0133	18		PA		6-6	33-22-51		D15360		A		GD03808	ST..	1		YN501
0141	18		PA		1-6	33-22-51		D15358		B		SM00004		S		YN501
0142	18		PA		6-6	33-22-51		D15358		C		GD04002	AC..	1		YN501
0143	18		PA		6-6	33-22-51		D15358		A		GD04002	ST..	1		YN501
0144	18		PA		13-5	33-22-51		D14994		B		SM00007		S		YR301-YR314, YR317-YR318, YR320-YR328
0145	18		PA		6-6	33-22-51		D14994		C		GD08022	AC..	1		YR301-YR314, YR317-YR318, YR320-YR328
0146	18		PA		6-6	33-22-51		D14994		A		GD08022	ST..	1		YR301-YR314, YR317-YR318, YR320-YR328
0154	18		PA		5-2	33-22-51		D14992		B		SM00018		S		YR301-YR314, YR317-YR318, YR320-YR328
0154	18		PA		5-2	33-22-51		D14992		B		SM00008		S		YR315-YR316, YR319
0155	18		PA		6-6	33-22-51		D14992		C		GD08030	AC..	1		YR301-YR328
0156	18		PA		6-6	33-22-51		D14992		A		GD08030	ST..	1		YR301-YR328
0164	18		PA		3-3	33-22-51		D14990		B		SM00018		S		YR301-YR314, YR317-YR318, YR320-YR328
0164	18		PA		3-8	33-22-51		D14990		B		SM00009		S		YR315-YR316, YR319
0165	18		PA		6-6	33-22-51		D14990		C		GD03808	AC..	1		YR301-YR328
0166	18		PA		6-6	33-22-51		D14990		A		GD03808	ST..	1		YR301-YR328
0201	18		PA		4-5	33-22-31		D14494		B		SM00011		S		YN501
0202	18		PA		6-6	33-22-31		D14494		C		GD03846	AC..	1		YN501
0203	18		PA		6-6	33-22-31		D14494		A		GD03846	ST..	1		YN501
0204	18		PA		5-5	33-22-31		D41066J		A		SM00011		S		YN501
0204	18		PA		8-2	33-22-31		D41066J		A		SM00011		S		YR301-YR328
0205	18		PA		6-1	33-22-31		SM00011		S		SM00012		S		YN501

WIRE LIST

D280A108

91-21-11

Section W4160

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4166		286A4166			LED LIGHTING - CEILING/WASH RIGHT (continued)											
0206		18		PA		11-1	33-22-31	SM00013		S		SM00012		S		YN501
0208		18		PA		9-4	33-22-31	SM00011		S		SM00015		S		YR301-YR328
0209		18		PA		6-3	33-22-31	SM00015		S		SM00016		S		YR301-YR328
0210		18		PA		10-1	33-22-31	SM00016		S		SM00017		S		YR301-YR328
0211		18		PA		3-10	33-22-31	D14502		B		SM00012		S		YN501
0212		18		PA		6-6	33-22-31	D14502		C		GD03846	AC..	1		YN501
0213		18		PA		6-6	33-22-31	D14502		A		GD03846	ST..	1		YN501
0214		18		PA		3-6	33-22-31	D14904		B		SM00011		S		YR301-YR328
0215		18		PA		6-6	33-22-31	D14904		C		GD08058	AC..	1		YR301-YR328
0216		18		PA		6-6	33-22-31	D14904		A		GD08058	ST..	1		YR301-YR328
0221		18		PA		4-1	33-22-31	D14506		B		SM00012		S		YN501
0222		18		PA		6-6	33-22-31	D14506		C		GD03868	AC..	1		YN501
0223		18		PA		6-6	33-22-31	D14506		A		GD03868	ST..	1		YN501
0244		18		PA		3-5	33-22-31	D14916		B		SM00015		S		YR301-YR328
0245		18		PA		6-6	33-22-31	D14916		C		GD03868	AC..	1		YR301-YR328
0246		18		PA		6-6	33-22-31	D14916		A		GD03868	ST..	1		YR301-YR328
0254		18		PA		3-4	33-22-31	D14918		B		SM00016		S		YR301-YR328
0255		18		PA		6-6	33-22-31	D14918		C		GD08014	AC..	1		YR301-YR328
0256		18		PA		6-6	33-22-31	D14918		A		GD08014	ST..	1		YR301-YR328
0261		18		PA		3-11	33-22-31	D14510		B		SM00013		S		YN501
0262		18		PA		6-6	33-22-31	D14510		C		GD03872	AC..	1		YN501
0263		18		PA		6-6	33-22-31	D14510		A		GD03872	ST..	1		YN501
0264		18		PA		9-1	33-22-31	D14920		B		SM00016		S		YR301-YR328
0265		18		PA		6-6	33-22-31	D14920		C		GD08018	AC..	1		YR301-YR328
0266		18		PA		6-6	33-22-31	D14920		A		GD08018	ST..	1		YR301-YR328
0271		18		PA		3-11	33-22-31	D14514		B		SM00013		S		YN501
0272		18		PA		6-6	33-22-31	D14514		C		GD03750	AC..	1		YN501
0273		18		PA		6-6	33-22-31	D14514		A		GD03750	ST..	1		YN501
0274		18		PA		4-0	33-22-31	D14922		B		SM00017		S		YR301-YR328
0275		18		PA		6-6	33-22-31	D14922		C		GD03750	AC..	1		YR301-YR328
0276		18		PA		6-6	33-22-31	D14922		A		GD03750	ST..	1		YR301-YR328
0281		18		PA		9-8	33-22-31	D14518		B		SM00013		S		YN501
0282		18		PA		6-6	33-22-31	D14518		C		GD03798	AC..	1		YN501
0283		18		PA		6-6	33-22-31	D14518		A		GD03798	ST..	1		YN501
0284		18		PA		9-10	33-22-31	D14924		B		SM00017		S		YR301-YR328
0285		18		PA		6-6	33-22-31	D14924		C		GD03798	AC..	1		YR301-YR328
0286		18		PA		6-6	33-22-31	D14924		A		GD03798	ST..	1		YR301-YR328
0304		18		PA		7-4	33-22-32	D41084J		A		SM00021		S		YN501
0306		18		PA		2-2	33-22-32	D41084J		A		SM00023		S		YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4160

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4166	286A4166				LED LIGHTING - CEILING/WASH RIGHT (continued)										
0307	18		PA		0-7	33-22-32	SM00023		S		SM00024		S		YR301-YR328
0308	18		PA		5-3	33-22-32	SM00024		S		SM00025		S		YR301-YR328
0309	18		PA		16-6	33-22-32	SM00025		S		SM00026		S		YR315-YR316, YR319
0310	18		PA		12-9	33-22-32	SM00021		S		SM00027		S		YN501
0324	18		PA		5-4	33-22-32	D14932		B		SM00023		S		YR315-YR316, YR319
0325	18		PA		6-6	33-22-32	D14932		C		GD03806	AC..	1		YR315-YR316, YR319
0326	18		PA		6-6	33-22-32	D14932		A		GD03806	ST..	1		YR315-YR316, YR319
0331	18		PA		10-3	33-22-32	D15334		B		SM00021		S		YN501
0332	18		PA		6-6	33-22-32	D15334		C		GD04008	AC..	1		YN501
0333	18		PA		6-6	33-22-32	D15334		A		GD04008	ST..	1		YN501
0341	18		PA		4-6	33-22-32	D15336		B		SM00021		S		YN501
0342	18		PA		6-6	33-22-32	D15336		C		GD03806	AC..	1		YN501
0343	18		PA		6-6	33-22-32	D15336		A		GD03806	ST..	1		YN501
0344	18		PA		8-9	33-22-32	D14940		B		SM00024		S		YR301-YR314, YR317-YR318, YR320-YR328
0345	18		PA		6-6	33-22-32	D14940		C		GD03806	AC..	1		YR301-YR314, YR317-YR318, YR320-YR328
0346	18		PA		6-6	33-22-32	D14940		A		GD03806	ST..	1		YR301-YR314, YR317-YR318, YR320-YR328
0351	18		PA		11-7	33-22-32	D15338		B		SM00027		S		YN501
0352	18		PA		6-6	33-22-32	D15338		C		GD08068	AC..	1		YN501
0353	18		PA		6-6	33-22-32	D15338		A		GD08068	ST..	1		YN501
0354	18		PA		13-5	33-22-32	D14942		B		SM00024		S		YR301-YR314, YR317-YR318, YR320-YR328
0354	18		PA		8-8	33-22-32	D14942		B		SM00025		S		YR315-YR316, YR319
0355	18		PA		6-6	33-22-32	D14942		C		GD08022	AC..	1		YR301-YR328
0356	18		PA		6-6	33-22-32	D14942		A		GD08022	ST..	1		YR301-YR328
0361	18		PA		6-6	33-22-32	D15340		B		SM00027		S		YN501
0362	18		PA		6-6	33-22-32	D15340		C		GD03808	AC..	1		YN501
0363	18		PA		6-6	33-22-32	D15340		A		GD03808	ST..	1		YN501
0364	18		PA		14-3	33-22-32	D14944		B		SM00025		S		YR301-YR314, YR317-YR318, YR320-YR328
0364	18		PA		5-2	33-22-32	D14944		B		SM00026		S		YR315-YR316, YR319
0365	18		PA		6-6	33-22-32	D14944		C		GD08026	AC..	1		YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4160

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4166		286A4166			LED LIGHTING - CEILING/WASH RIGHT (continued)											
0366		18		PA		6-6	33-22-32	D14944		A		GD08026	ST..	1		YR301-YR328
0371		18		PA		2-10	33-22-32	D15346		B		SM00027		S		YN501
0372		18		PA		6-6	33-22-32	D15346		C		GD04002	AC..	1		YN501
0373		18		PA		6-6	33-22-32	D15346		A		GD04002	ST..	1		YN501
0374		18		PA		19-2	33-22-32	D15388		B		SM00025		S		YR301-YR314, YR317-YR318, YR320-YR328
0374		18		PA		3-3	33-22-32	D15388		B		SM00026		S		YR315-YR316, YR319
0375		18		PA		6-6	33-22-32	D15388		C		GD03808	AC..	1		YR301-YR328
0376		18		PA		6-6	33-22-32	D15388		A		GD03808	ST..	1		YR301-YR328
0384		18		PA		23-8	33-22-32	D14952		B		SM00025		S		YR301-YR314, YR317-YR318, YR320-YR328
0384		18		PA		8-3	33-22-32	D14952		B		SM00026		S		YR315-YR316, YR319
0385		18		PA		6-6	33-22-32	D14952		C		GD04002	AC..	1		YR301-YR328
0386		18		PA		6-6	33-22-32	D14952		A		GD04002	ST..	1		YR301-YR328
0424		18		PA		4-9	33-22-31	D14784		B		SM00015		S		YR301-YR328
0425		18		PA		6-6	33-22-31	D14784		C		GD03862	AC..	1		YR301-YR328
0426		18		PA		6-6	33-22-31	D14784		A		GD03862	ST..	1		YR301-YR328
0434		18		PA		5-4	33-22-32	D15292		B		SM00023		S		YR301-YR314, YR317-YR318, YR320-YR328
0435		18		PA		6-6	33-22-32	D15292		C		GD03804	AC..	1		YR301-YR314, YR317-YR318, YR320-YR328
0436		18		PA		6-6	33-22-32	D15292		A		GD03804	ST..	1		YR301-YR314, YR317-YR318, YR320-YR328
0444		18		PA		2-10	33-22-32	D15294		B		SM00023		S		YR301-YR314, YR317-YR318, YR320-YR328
0445		18		PA		6-6	33-22-32	D15294		C		GD03806	AC..	1		YR301-YR314, YR317-YR318, YR320-YR328
0446		18		PA		6-6	33-22-32	D15294		A		GD03806	ST..	1		YR301-YR314, YR317-YR318, YR320-YR328
0510		18		PA		12-2	SPARE	D41088P		3		D41066J		C		YN501
0510		18		PA		12-3	SPARE	D41088P		3		D41066J		C		YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4160

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4166	286A4166				LED LIGHTING - CEILING/WASH RIGHT (continued)											
0511	20		PA		6-0	33-26-31		D41088P		1		D07162J	= 1	VY		YN501
0511	20		PA		6-1	33-26-31		D41088P		1		D07162J	= 1	VY		YR301-YR328
0512	18		PA		4-1	33-26-31		D41088P		2		GD11108	AC..	1		YN501
0512	18		PA		4-2	33-26-31		D41088P		2		GD11108	AC..	1		YR301-YR328
0524	18		PA		2-1	33-22-31		D15382		B		SM00011		S		YR301-YR328
0525	18		PA		6-6	33-22-31		D15382		C		GD03846	AC..	1		YR301-YR328
0526	18		PA		6-6	33-22-31		D15382		A		GD03846	ST..	1		YR301-YR328
0534	18		PA		10-8	33-22-32		D15248		B		SM00024		S		YR315-YR316, YR319
0535	18		PA		4-5	33-22-32		D15248		C		GD03882	AC..	1		YR315-YR316, YR319
0536	18		PA		4-5	33-22-32		D15248		A		GD03882	ST..	1		YR315-YR316, YR319
0544	18		PA		4-0	33-22-32		D15386		B		SM00025		S		YR315-YR316, YR319
0545	18		PA		6-6	33-22-32		D15386		C		GD03806	AC..	1		YR315-YR316, YR319
0546	18		PA		6-6	33-22-32		D15386		A		GD03806	ST..	1		YR315-YR316, YR319
0554	18		PA		2-10	33-22-51		D15404		B		SM00010		S		YR301-YR314, YR317-YR318, YR320-YR328
0554	18		PA		2-10	33-22-51		D15404		B		SM00009		S		YR315-YR316, YR319
0555	18		PA		6-6	33-22-51		D15404		C		GD04002	AC..	1		YR301-YR328
0556	18		PA		6-6	33-22-51		D15404		A		GD04002	ST..	1		YR301-YR328
0564	18		PA		11-3	33-22-51		D15406		B		SM00008		S		YR315-YR316, YR319
0565	18		PA		6-6	33-22-51		D15406		C		GD08022	AC..	1		YR315-YR316, YR319
0566	18		PA		6-6	33-22-51		D15406		A		GD08022	ST..	1		YR315-YR316, YR319
0574	18		PA		7-3	33-22-51		D15412		B		SM00019		S		YR301-YR328
0575	18		PA		6-6	33-22-51		D15412		C		GD03862	AC..	1		YR301-YR328
0576	18		PA		6-6	33-22-51		D15412		A		GD03862	ST..	1		YR301-YR328
0604	18		PA		2-10	33-22-51		D15310		B		SM00007		S		YR301-YR314, YR317-YR318, YR320-YR328
0605	18		PA		6-6	33-22-51		D15310		C		GD07226	AC..	1		YR301-YR314, YR317-YR318, YR320-YR328
0606	18		PA		6-6	33-22-51		D15310		A		GD07226	ST..	1		YR301-YR314, YR317-YR318, YR320-YR328
0614	18		PA		8-9	33-22-51		D15308		B		SM00007		S		YR301-YR314, YR317-YR318, YR320-YR328

WIRE LIST
D280A108

91-21-11
Section W4160
Page 10
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4166	286A4166			LED LIGHTING - CEILING/WASH RIGHT (continued)											
0615	18		PA		6-6	33-22-51	D15308		C		GD03806	AC..	1		YR301-YR314, YR317-YR318, YR320-YR328
0616	18		PA		6-6	33-22-51	D15308		A		GD03806	ST..	1		YR301-YR314, YR317-YR318, YR320-YR328
2003B	24		OT	EC	9-10	33-22-31	D41062J		2		D14496		2		YN501
2003B	24		OT	EC	9-6	33-22-31	D41062J		2		D14902		2		YR301-YR328
2003W	24		OT	EC	0-0	33-22-31	D41062J		1		D14496		1		YN501
2003W	24		OT	EC	0-0	33-22-31	D41062J		1		D14902		1		YR301-YR328
2003Z				EC	0-0	33-22-31	D41062J		5		D14496		5		YN501
2003Z				EC	0-0	33-22-31	D41062J		5		D14902		5		YR301-YR328
2004B	24		PL	ED	9-10	33-22-31	D41062J		4		D14496		4		YN501
2004B	24		PL	ED	9-6	33-22-31	D41062J		4		D14902		4		YR301-YR328
2004R	24		PL	ED	0-0	33-22-31	D41062J		3		D14496		3		YN501
2004R	24		PL	ED	0-0	33-22-31	D41062J		3		D14902		3		YR301-YR328
2005B	24		OT	EE	6-5	33-22-31	D14500		2		D14504		2		YN501
2005W	24		OT	EE	0-0	33-22-31	D14500		1		D14504		1		YN501
2005Z				EE	0-0	33-22-31	D14500		5		D14504		5		YN501
2006B	24		PL	EF	6-5	33-22-31	D14500		4		D14504		4		YN501
2006R	24		PL	EF	0-0	33-22-31	D14500		3		D14504		3		YN501
2017B	24		OT	ER	11-4	33-22-32	D15368		2		D14930		2		YR315-YR316, YR319
2017W	24		OT	ER	0-0	33-22-32	D15368		1		D14930		1		YR315-YR316, YR319
2017Z				ER	0-0	33-22-32	D15368		5		D14930		5		YR315-YR316, YR319
2018B	24		PL	ES	11-4	33-22-32	D15368		4		D14930		4		YR315-YR316, YR319
2018R	24		PL	ES	0-0	33-22-32	D15368		3		D14930		3		YR315-YR316, YR319
2021B	24		OT	EV	3-11	33-22-32	D15414		2		D14950		2		YR301-YR328
2021W	24		OT	EV	0-0	33-22-32	D15414		1		D14950		1		YR301-YR328
2021Z				EV	0-0	33-22-32	D15414		5		D14950		5		YR301-YR328
2022B	24		PL	EW	3-11	33-22-32	D15414		4		D14950		4		YR301-YR328
2022R	24		PL	EW	0-0	33-22-32	D15414		3		D14950		3		YR301-YR328
2045B	24		OT	HU	11-0	33-22-32	D15246		2		D15244		2		YR315-YR316, YR319
2045W	24		OT	HU	0-0	33-22-32	D15246		1		D15244		1		YR315-YR316, YR319
2045Z				HU	0-0	33-22-32	D15246		5		D15244		5		YR315-YR316, YR319
2046B	24		PL	HV	11-0	33-22-32	D15246		4		D15244		4		YR315-YR316, YR319
2046R	24		PL	HV	0-0	33-22-32	D15246		3		D15244		3		YR315-YR316, YR319
2047B	24		OT	HW	3-9	33-22-32	D15384		2		D15250		2		YR315-YR316, YR319
2047W	24		OT	HW	0-0	33-22-32	D15384		1		D15250		1		YR315-YR316, YR319
2047Z				HW	0-0	33-22-32	D15384		5		D15250		5		YR315-YR316, YR319

WIRE LIST

D280A108

91-21-11

Section W4160

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4166	286A4166			LED LIGHTING - CEILING/WASH RIGHT (continued)											
2048B	24	PL	HX		3-9	33-22-32	D15384		4		D15250		4		YR315-YR316, YR319
2048R	24	PL	HX		0-0	33-22-32	D15384		3		D15250		3		YR315-YR316, YR319
2049B	24	OT	HY		4-1	33-22-51	D14954		2		D15402		2		YR301-YR328
2049W	24	OT	HY		0-0	33-22-51	D14954		1		D15402		1		YR301-YR328
2049Z			HY		0-0	33-22-51	D14954		5		D15402		5		YR301-YR328
2050B	24	PL	HZ		4-1	33-22-51	D14954		4		D15402		4		YR301-YR328
2050R	24	PL	HZ		0-0	33-22-51	D14954		3		D15402		3		YR301-YR328
2051B	24	OT	IA		13-4	33-22-51	D15418		2		D15408		2		YR315-YR316, YR319
2051W	24	OT	IA		0-0	33-22-51	D15418		1		D15408		1		YR315-YR316, YR319
2051Z			IA		0-0	33-22-51	D15418		5		D15408		5		YR315-YR316, YR319
2052B	24	PL	IB		13-4	33-22-51	D15418		4		D15408		4		YR315-YR316, YR319
2052R	24	PL	IB		0-0	33-22-51	D15418		3		D15408		3		YR315-YR316, YR319
2053B	24	OT	IC		5-5	33-22-31	D14906		2		D15380		2		YR301-YR328
2053W	24	OT	IC		0-0	33-22-31	D14906		1		D15380		1		YR301-YR328
2053Z			IC		0-0	33-22-31	D14906		5		D15380		5		YR301-YR328
2054B	24	PL	ID		5-5	33-22-31	D14906		4		D15380		4		YR301-YR328
2054R	24	PL	ID		0-0	33-22-31	D14906		3		D15380		3		YR301-YR328
2055B	24	OT	GE		3-10	33-22-32	D15344		2		D15342		2		YN501
2055W	24	OT	GE		0-0	33-22-32	D15344		1		D15342		1		YN501
2055Z			GE		0-0	33-22-32	D15344		5		D15342		5		YN501
2056B	24	PL	GF		3-10	33-22-32	D15344		4		D15342		4		YN501
2056R	24	PL	GF		0-0	33-22-32	D15344		3		D15342		3		YN501
2057B	24	OT	GG		4-2	33-22-51	D15348		2		D15356		2		YN501
2057W	24	OT	GG		0-0	33-22-51	D15348		1		D15356		1		YN501
2057Z			GG		0-0	33-22-51	D15348		5		D15356		5		YN501
2058B	24	PL	GH		4-2	33-22-51	D15348		4		D15356		4		YN501
2058R	24	PL	GH		0-0	33-22-51	D15348		3		D15356		3		YN501

WIRE LIST

D280A108

91-21-11
Section W4160
Page 12 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4170	286A4170	AB0420A TO E3-1 SHELF													
1301R	20	X5	EN	16-3	26-11-21	D40728P		22			D40732P	B19			ALL
1301Z			EN	0-0	26-11-21	D40728P		S/R			D40732P	PERG	1F		ALL
1302R	20	X5	EP	16-3	26-11-21	D40728P		23			D40732P	A19			ALL
1302Z			EP	0-0	26-11-21	D40728P		S/R			D40732P	PERG	1F		ALL
2601B	22	PB	SA	16-3	78-36-21	D40730P		1			D40732P	A01			ALL
2601R	22	PB	SA	0-0	78-36-21	D40730P		2			D40732P	B01			ALL
2602B	22	PB	SB	16-3	78-36-21	D40730P		3			D40732P	A02			ALL
2602R	22	PB	SB	0-0	78-36-21	D40730P		4			D40732P	B02			ALL
2603B	24	Y2	SC	16-3	73-24-12	D40730P		5			D40732P	A03			ALL
2603R	24	Y2	SC	0-0	73-24-12	D40730P		6			D40732P	B03			ALL
2603Z			SC	0-0	73-24-12	D40730P		S/R			D40732P	PERG	1F		ALL
2604B	24	Y2	SD	16-3	73-24-21	D40730P		7			D40732P	A04			ALL
2604R	24	Y2	SD	0-0	73-24-21	D40730P		8			D40732P	B04			ALL
2604Z			SD	0-0	73-24-21	D40730P		S/R			D40732P	PERG	1F		ALL
2605B	20	PB	SE	16-3	SPARE	D40730P		9			D40732P	A05			ALL
2605R	20	PB	SE	0-0	SPARE	D40730P		10			D40732P	B05			ALL
2606B	20	PB	SF	16-3	SPARE	D40730P		11			D40732P	A06			ALL
2606R	20	PB	SF	0-0	SPARE	D40730P		12			D40732P	B06			ALL
2607B	22	VX	SG	16-3	77-31-21	D40728P		1			D40732P	A07			ALL
2607W	22	VX	SG	0-0	77-31-21	D40728P		2			D40732P	B07			ALL
2607Z			SG	0-0	77-31-21	D40728P		3			D40732P	A08			ALL
2608B	24	Y2	SH	16-3	77-12-11	D40728P		4			D40732P	A09			ALL
2608R	24	Y2	SH	0-0	77-12-11	D40728P		5			D40732P	B09			ALL
2608Z			SH	0-0	77-12-11	D40728P		S/R			D40732P	PERG	1F		ALL
2609B	20	PB	SJ	16-3	SPARE	D40728P		6			D40732P	A10			ALL
2609R	20	PB	SJ	0-0	SPARE	D40728P		7			D40732P	B10			ALL
3601B	24	Y3	A4	16-3	79-31-11	D40728P		12			D40732P	A13			ALL
3601R	24	Y3	A4	0-0	79-31-11	D40728P		13			D40732P	B13			ALL
3601Y	24	Y3	A4	0-0	79-31-11	D40728P		14			D40732P	A14			ALL
3601Z			A4	0-0	79-31-11	D40728P		S/R			D40732P	PERG	1F		ALL
6501	24	PK		16-3	31-62-24	D40732P		A16			D40728P	17			ALL
6502	24	PK		16-3	31-62-24	D40728P		10			D40732P	B14			ALL

WIRE LIST

D280A108

91-21-11

Section W4170

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4180	286A4180			AFT PASS CAB TEMP SENSOR (M1446) TO STA 7XX (CEILING)											
0001	24	PK		7-1	21-61-14	D41834J		1			D03912	1			YC051-YL999
0002	20	PA		7-1	21-61-14	D41834J		6			D03912	2			YC051-YL999
0003	20	PA		7-1	21-61-14	D41834J		7			D03912	3			YC051-YL999
0004	20	PA		5-3	21-61-51	D41834J		8			D03922	A			YC051-YL999
0005	20	PA		5-3	21-61-51	D41834J		9			D03922	B			YC051-YL999
2001B	24	PL	GA	5-3	21-61-14	D41834J		2			D03910	1			YC051-YL999
2001R	24	PL	GA	0-0	21-61-14	D41834J		3			D03910	2			YC051-YL999
2002B	24	PL	GB	5-3	21-61-14	D41834J		5			D03910	4			YC051-YL999
2002R	24	PL	GB	0-0	21-61-14	D41834J		4			D03910	3			YC051-YL999

WIRE LIST

D280A108

91-21-11

Section W4180

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4190		286A4190				P18/EE BAY TO ZONAL DRYER									
0001	14		CQ		105-6	21-74-11	D13740				D40208P	14			YD158-YD170
0002	14		CQ		105-6	21-74-11	D13740				D40208P	16			YD158-YD170
0003	14		CQ		105-6	21-74-11	D13740				D40208P	18			YD158-YD170
0004	14		PA		3-10	21-74-11	D13740				GD00872	AC..	E		YD158-YD170
0005	20		PA		23-6	21-74-11	D13738				D13742	A			YD158-YD170
0006	20		PA		23-6	21-74-11	D13738				D13742	B			YD158-YD170
0007	20		PA		23-6	21-74-11	D13738				D13742	C			YD158-YD170
0008	20		PA		9-3	21-74-11	D13738				GD00028	DC..	1		YD158-YD170
0010	22		PA		124-7	21-74-11	D13738				D13736	1			YD158-YD170
0011	22		PA		124-7	21-74-11	D13738				D13736	2			YD158-YD170
0012	22		PA		124-7	21-74-11	D13738				D13736	7			YD158-YD170
0013	22		PA		124-7	21-74-11	D13738				D13736	8			YD158-YD170
0014	22		PA		124-7	21-74-11	D13738				D13736	9			YD158-YD170
0015	22		PA		124-7	21-74-11	D13738				D13736	5			YD158-YD170
0016	22		PA		124-7	21-74-11	D13738				D13736	6			YD158-YD170
0017	22		PA		124-7	21-74-11	D13738				D13736	3			YD158-YD170
0018	20		PA		60-0	21-74-11	D13736				D40208P	1			YD158-YD170
0019	20		PA		16-1	21-74-11	D13736				GD00427	DC..	1A		YD158-YD170
0020	20		PA		60-0	21-74-11	D13736				D40208P	2			YD158-YD170
0021	12		PA		1-10	21-74-11	M02542	GND1	E		GD00876	ST..	E		YD158-YD170
W4192		286A4192				NS/FSB SIGN-VIDEO PANEL, FORWARD-RIGHT									
3201B	20		PC	YA	4-6	33-25-61	D12017				SM00201		S		YL951-YL999
3201B	20		PC	YA	4-8	33-25-61	D12017				SM00201		S		YN231-YN260
3201R	20		PC	YA	0-0	33-25-61	D12017				SM00101		S		YL951-YN260
3201Y	20		PC	YA	0-0	33-25-61	D12017				SM00301		S		YL951-YN260
3203B	20		PC	YC	6-3	33-25-61	D12029				SM00203		S		YL951-YL999
3203B	20		PC	YC	6-4	33-25-61	D12029				SM00203		S		YN231-YN260
3203R	20		PC	YC	0-0	33-25-61	D12029				SM00103		S		YL951-YN260
3203Y	20		PC	YC	0-0	33-25-61	D12029				SM00303		S		YL951-YN260
3205B	20		PC	YE	6-0	33-25-61	D12041				SM00205		S		YL951-YN260
3205R	20		PC	YE	0-0	33-25-61	D12041				SM00105		S		YL951-YN260
3205Y	20		PC	YE	0-0	33-25-61	D12041				SM00305		S		YL951-YN260
3207B	20		PC	YG	4-4	33-25-61	D12053				SM00207		S		YL951-YL999
3207R	20		PC	YG	0-0	33-25-61	D12053				SM00107		S		YL951-YL999
3207Y	20		PC	YG	0-0	33-25-61	D12053				SM00307		S		YL951-YL999
3209B	20		PC	YI	5-2	33-25-61	D12065				SM00209		S		YL951-YL999
3209B	20		PC	YI	6-10	33-25-61	D12065				SM00209		S		YN231-YN260
3209R	20		PC	YI	0-0	33-25-61	D12065				SM00109		S		YL951-YN260

WIRE LIST

D280A108

91-21-11

Section W4190

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4192	286A4192			NS/FSB SIGN-VIDEO PANEL, FORWARD-RIGHT (continued)											
3209Y	20	PC	YI		0-0	33-25-61	D12065		3		SM00309		S		YL951-YN260
3211B	20	PC	YK		4-3	33-25-61	D12077		2		SM00211		S		YL951-YL999
3211B	20	PC	YK		11-4	33-25-61	D12077		2		SM00209		S		YN231-YN260
3211R	20	PC	YK		0-0	33-25-61	D12077		1		SM00111		S		YL951-YL999
3211R	20	PC	YK		0-0	33-25-61	D12077		1		SM00109		S		YN231-YN260
3211Y	20	PC	YK		0-0	33-25-61	D12077		3		SM00311		S		YL951-YL999
3211Y	20	PC	YK		0-0	33-25-61	D12077		3		SM00309		S		YN231-YN260
3213B	20	PC	YM		11-7	33-25-61	D12089		2		SM00211		S		YL951-YL999
3213R	20	PC	YM		0-0	33-25-61	D12089		1		SM00111		S		YL951-YL999
3213Y	20	PC	YM		0-0	33-25-61	D12089		3		SM00311		S		YL951-YL999
3215B	20	PC	YP		9-11	33-25-61	D40862J		2		SM00201		S		YL951-YL999
3215B	20	PC	YP		9-5	33-25-61	D40862J		2		SM00201		S		YN231-YN260
3215R	20	PC	YP		0-0	33-25-61	D40862J		1		SM00101		S		YL951-YN260
3215Y	20	PC	YP		0-0	33-25-61	D40862J		3		SM00301		S		YL951-YN260
3217B	20	PC	YR		6-1	33-25-61	SM00201			S	SM00203		S		YL951-YL999
3217B	20	PC	YR		6-2	33-25-61	SM00201			S	SM00203		S		YN231-YN260
3217R	20	PC	YR		0-0	33-25-61	SM00101			S	SM00103		S		YL951-YN260
3217Y	20	PC	YR		0-0	33-25-61	SM00301			S	SM00303		S		YL951-YN260
3219B	20	PC	YT		4-6	33-25-61	SM00203			S	SM00205		S		YL951-YL999
3219B	20	PC	YT		4-2	33-25-61	SM00203			S	SM00205		S		YN231-YN260
3219R	20	PC	YT		0-0	33-25-61	SM00103			S	SM00105		S		YL951-YN260
3219Y	20	PC	YT		0-0	33-25-61	SM00303			S	SM00305		S		YL951-YN260
3221B	20	PC	YV		3-11	33-25-61	SM00205			S	SM00207		S		YL951-YL999
3221R	20	PC	YV		0-0	33-25-61	SM00105			S	SM00107		S		YL951-YL999
3221Y	20	PC	YV		0-0	33-25-61	SM00305			S	SM00307		S		YL951-YL999
3223B	20	PC	YX		4-1	33-25-61	SM00207			S	SM00209		S		YL951-YL999
3223B	20	PC	YX		7-5	33-25-61	SM00205			S	SM00209		S		YN231-YN260
3223R	20	PC	YX		0-0	33-25-61	SM00107			S	SM00109		S		YL951-YL999
3223R	20	PC	YX		0-0	33-25-61	SM00105			S	SM00109		S		YN231-YN260
3223Y	20	PC	YX		0-0	33-25-61	SM00307			S	SM00309		S		YL951-YL999
3223Y	20	PC	YX		0-0	33-25-61	SM00305			S	SM00309		S		YN231-YN260
3225B	20	PC	YZ		8-5	33-25-61	SM00209			S	SM00211		S		YL951-YL999
3225R	20	PC	YZ		0-0	33-25-61	SM00109			S	SM00111		S		YL951-YL999
3225Y	20	PC	YZ		0-0	33-25-61	SM00309			S	SM00311		S		YL951-YL999
W4194	286A4194			NS/FSB SIGN-VIDEO PANEL, AFT-RIGHT											
3201B	20	PC	YA		3-4	33-25-61	D12101		2		SM00201		S		YL951-YL999
3201B	20	PC	YA		3-7	33-25-61	D12101		2		SM00201		S		YN231-YN260
3201R	20	PC	YA		0-0	33-25-61	D12101		1		SM00101		S		YL951-YN260

WIRE LIST

D280A108

91-21-11

Section W4190

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Diagram	From				To				Effectivity
	Wire No.	GA	CO TY			Fam	FT-IN	Equip	Term	Type	Splice	Equip	Term	
W4194	286A4194			NS/FSB SIGN-VIDEO PANEL, AFT-RIGHT (continued)										
3201Y	20	PC	YA		0-0	33-25-61	D12101		3		SM00301		S	YL951-YN260
3203B	20	PC	YC		4-6	33-25-61	D12113		2		SM00203		S	YL951-YL999
3203B	20	PC	YC		4-10	33-25-61	D12113		2		SM00203		S	YN231-YN260
3203R	20	PC	YC		0-0	33-25-61	D12113		1		SM00103		S	YL951-YN260
3203Y	20	PC	YC		0-0	33-25-61	D12113		3		SM00303		S	YL951-YN260
3205B	20	PC	YE		4-6	33-25-61	D12125		2		SM00205		S	YL951-YL999
3205R	20	PC	YE		0-0	33-25-61	D12125		1		SM00105		S	YL951-YL999
3205Y	20	PC	YE		0-0	33-25-61	D12125		3		SM00305		S	YL951-YL999
3207B	20	PC	YG		6-0	33-25-61	D12137		2		SM00207		S	YL951-YL999
3207B	20	PC	YG		5-4	33-25-61	D12137		2		SM00207		S	YN231-YN260
3207R	20	PC	YG		0-0	33-25-61	D12137		1		SM00107		S	YL951-YN260
3207Y	20	PC	YG		0-0	33-25-61	D12137		3		SM00307		S	YL951-YN260
3209B	20	PC	YI		6-1	33-25-61	D12149		2		SM00209		S	YL951-YL999
3209B	20	PC	YI		11-8	33-25-61	D12149		2		SM00207		S	YN231-YN260
3209R	20	PC	YI		0-0	33-25-61	D12149		1		SM00109		S	YL951-YL999
3209R	20	PC	YI		0-0	33-25-61	D12149		1		SM00107		S	YN231-YN260
3209Y	20	PC	YI		0-0	33-25-61	D12149		3		SM00309		S	YL951-YL999
3209Y	20	PC	YI		0-0	33-25-61	D12149		3		SM00307		S	YN231-YN260
3211B	20	PC	YK		10-10	33-25-61	D12161		2		SM00209		S	YL951-YL999
3211R	20	PC	YK		0-0	33-25-61	D12161		1		SM00109		S	YL951-YL999
3211Y	20	PC	YK		0-0	33-25-61	D12161		3		SM00309		S	YL951-YL999
3215B	20	PC	YP		2-3	33-25-61	D40864J		2		SM00201		S	YL951-YL999
3215B	20	PC	YP		2-1	33-25-61	D40864J		2		SM00201		S	YN231-YN260
3215R	20	PC	YP		0-0	33-25-61	D40864J		1		SM00101		S	YL951-YN260
3215Y	20	PC	YP		0-0	33-25-61	D40864J		3		SM00301		S	YL951-YN260
3217B	20	PC	YR		6-8	33-25-61	SM00201		S		SM00203		S	YL951-YL999
3217B	20	PC	YR		7-10	33-25-61	SM00201		S		SM00203		S	YN231-YN260
3217R	20	PC	YR		0-0	33-25-61	SM00101		S		SM00103		S	YL951-YN260
3217Y	20	PC	YR		0-0	33-25-61	SM00301		S		SM00303		S	YL951-YN260
3219B	20	PC	YT		6-1	33-25-61	SM00203		S		SM00205		S	YL951-YL999
3219R	20	PC	YT		0-0	33-25-61	SM00103		S		SM00105		S	YL951-YL999
3219Y	20	PC	YT		0-0	33-25-61	SM00303		S		SM00305		S	YL951-YL999
3221B	20	PC	YV		7-3	33-25-61	SM00205		S		SM00207		S	YL951-YL999
3221B	20	PC	YV		9-2	33-25-61	SM00203		S		SM00207		S	YN231-YN260
3221R	20	PC	YV		0-0	33-25-61	SM00105		S		SM00107		S	YL951-YL999
3221R	20	PC	YV		0-0	33-25-61	SM00103		S		SM00107		S	YN231-YN260
3221Y	20	PC	YV		0-0	33-25-61	SM00305		S		SM00307		S	YL951-YL999
3221Y	20	PC	YV		0-0	33-25-61	SM00303		S		SM00307		S	YN231-YN260
3223B	20	PC	YX		9-1	33-25-61	SM00207		S		SM00209		S	YL951-YL999

WIRE LIST

D280A108

91-21-11

Section W4190

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4194	286A4194			NS/FSB SIGN-VIDEO PANEL, AFT-RIGHT (continued)											
3223R	20	PC	YX		0-0	33-25-61	SM00107				SM00109		S		YL951-YL999
3223Y	20	PC	YX		0-0	33-25-61	SM00307				SM00309		S		YL951-YL999

For training purposes only!

WIRE LIST
D280A108

91-21-11
Section W4190
Page 4 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4222	286A4222			AB1050R DISCONNECT BRACKET TO STAB TRIM ACTUATOR											
1001	20	VF	AA		9-8	27-41-12	SP00158			9	D40836J	1			YC053-YD153
1001	20	VF	AA		9-6	27-41-12	SP00158			9	D40836J	1			YD154-YN236, YN501-YR328
1001Z				AA	0-0	27-41-12	GD00060	ST..	1		D40836J	S/R			YC053-YD153
1001Z				AA	0-0	27-41-12	GD00036	ST..	1		D40836J	S/R			YD154-YN236, YN501-YR328
1002	20	VF	AB		9-8	27-41-12	SP00160			9	D40836J	2			YC053-YD153
1002	20	VF	AB		9-6	27-41-12	SP00160			9	D40836J	2			YD154-YN236, YN501-YR328
1002Z				AB	0-0	27-41-12	GD00060	ST..	1		D40836J	S/R			YC053-YD153
1002Z				AB	0-0	27-41-12	GD00036	ST..	1		D40836J	S/R			YD154-YN236, YN501-YR328
1003	20	VF	AC		9-8	27-41-12	SP00156			9	D40836J	3			YC053-YD153
1003	20	VF	AC		9-6	27-41-12	SP00156			9	D40836J	3			YD154-YN236, YN501-YR328
1003Z				AC	0-0	27-41-12	GD00060	ST..	1		D40836J	S/R			YC053-YD153
1003Z				AC	0-0	27-41-12	GD00036	ST..	1		D40836J	S/R			YD154-YN236, YN501-YR328
1004	18	VF	AD		16-10	27-41-12	D40836J		5	18	D00700	8			YC053-YD153
1004	18	VF	AD		16-7	27-41-12	D40836J		5	18	D00700	8			YD154-YD157
1004	18	VF	AD		16-8	27-41-12	D40836J		5	18	D00700	8			YD158-YL968, YN231-YN236, YN501-YR309
1004	18	VF	AD		16-9	27-41-12	D40836J		5	18	D00700	8			YL969-YL999, YR312-YR328
1004Z				AD	0-0	27-41-12	D40836J	S/R			GD04801	ST..	E	*2	YC053-YN236, YN501-YR328
1005	18	VF	AE		18-4	27-41-12	SP00154			9	D00700	6			YC053-YD153, YD158-YL968, YN231-YN236, YN501-YR309
1005	18	VF	AE		18-3	27-41-12	SP00154			9	D00700	6			YD154-YD157
1005	18	VF	AE		18-5	27-41-12	SP00154			9	D00700	6			YL969-YL999, YR312-YR328
1005Z				AE	0-0	27-41-12	GD00060	ST..	1		GD04801	ST..	E	*2	YC053-YD153
1005Z				AE	0-0	27-41-12	GD00036	ST..	1		GD04801	ST..	E	*2	YD154-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W4220

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4222	286A4222			AB1050R DISCONNECT BRACKET TO STAB TRIM ACTUATOR (continued)											
1006	18	VF	AF		18-4	27-41-12	SP00152		9		D00700	7			YC053-YD153, YD158-YL968, YN231-YN236, YN501-YR309
1006	18	VF	AF		18-3	27-41-12	SP00152		9		D00700	7			YD154-YD157
1006	18	VF	AF		18-5	27-41-12	SP00152		9		D00700	7			YL969-YL999, YR312-YR328
1006Z			AF		0-0	27-41-12	GD00060	ST..	1		GD04801	ST..	E	*2	YC053-YD153
1006Z			AF		0-0	27-41-12	GD00036	ST..	1		GD04801	ST..	E	*2	YD154-YN236, YN501-YR328
1008	18	VF	AG		6-0	27-41-12	GD00046	AC..	1		D00700	10			YC053-YD153
1008	18	VF	AG		5-4	27-41-12	GD00046	AC..	1		D00700	10			YD154-YD157
1008	18	VF	AG		5-5	27-41-12	GD00046	AC..	1		D00700	10			YD158-YL968, YN231-YN236, YN501-YR309
1008	18	VF	AG		6-1	27-41-12	GD00046	AC..	1		D00700	10			YL969-YL999, YR312-YR328
1008Z			AG		0-0	27-41-12	GD00046	AC..	1		GD04801	ST..	E	*3	YC053-YN236, YN501-YR328
1009	18	VF	AH		6-0	27-41-12	GD00046	DC..	1		D00700	5			YC053-YD153
1009	18	VF	AH		5-4	27-41-12	GD00046	DC..	1		D00700	5			YD154-YD157
1009	18	VF	AH		5-5	27-41-12	GD00046	DC..	1		D00700	5			YD158-YL968, YN231-YN236, YN501-YR309
1009	18	VF	AH		6-1	27-41-12	GD00046	DC..	1		D00700	5			YL969-YL999, YR312-YR328
1009Z			AH		0-0	27-41-12	GD00046	DC..	1		GD04801	ST..	E	*3	YC053-YN236, YN501-YR328
1010	18	PA			6-0	27-41-12	D00700		4		GD00046	ST..	1		YC053-YD153
1010	18	PA			5-4	27-41-12	D00700		4		GD00046	ST..	1		YD154-YD157
1010	18	PA			5-5	27-41-12	D00700		4		GD00046	ST..	1		YD158-YL968, YN231-YN236, YN501-YR309
1010	18	PA			6-1	27-41-12	D00700		4		GD00046	ST..	1		YL969-YL999, YR312-YR328
3201B	14	MZ	YA		16-10	27-41-12	D00700		3	14	D40836J	10	14		YC053-YD153
3201B	14	MZ	YA		16-7	27-41-12	D00700		3	14	D40836J	10	14		YD154-YD157

WIRE LIST

D280A108

91-21-11

Section W4220

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W4222	286A4222				AB1050R DISCONNECT BRACKET TO STAB TRIM ACTUATOR (continued)										
3201B	14		MZ	YA	16-8	27-41-12	D00700		3	14		D40836J	10	14	YD158-YL968, YN231-YN236, YN501-YR309
3201B	14		MZ	YA	16-9	27-41-12	D00700		3	14		D40836J	10	14	YL969-YL999, YR312-YR328
3201R	14		MZ	YA	0-0	27-41-12	D00700		1	14		D40836J	4	14	YC053-YN236, YN501-YR328
3201Y	14		MZ	YA	0-0	27-41-12	D00700		2	14		D40836J	7	14	YC053-YN236, YN501-YR328
A-A					0-0	27-41-12	S00844		2			S00844	CAP	Y	YC053-YN236, YN501-YR328
A-B					0-0	27-41-12	S00844		3			S00844	CAP	Y	YC053-YN236, YN501-YR328
A-C					0-0	27-41-12	S00844		5			S00844	CAP	Y	YC053-YN236, YN501-YR328
A-E					0-0	27-41-12	S00844		6			SP00154		9	YC053-YN236, YN501-YR328
A-F					0-0	27-41-12	S00145		6			SP00154		9	YC053-YN236, YN501-YR328
A-G					0-0	27-41-12	S00145		5			S00145	CAP	Y	YC053-YN236, YN501-YR328
A-H					0-0	27-41-12	S00844		1			S00844	CAP	Y	YC053-YN236, YN501-YR328
A-J					0-0	27-41-12	S00844		4			SP00158		9	YC053-YN236, YN501-YR328
A-K					0-0	27-41-12	S00145		4			SP00160		9	YC053-YN236, YN501-YR328
YAAA					0-0	27-41-12	GD04801	ST..	E	*2		D40836J	S/R		YC053-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W4220

Page 3 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4246	286A4246				LED LIGHTING - SIDEWALL RIGHT										
0001	18		PA		2-2	33-21-12	D14594		B		SM00001		S		YN501-YR328
0002	18		PA		4-9	33-21-12	D14594		C		GD03858	AC..	1D		YN501-YR328
0003	18		PA		4-9	33-21-12	D14594		A		GD03858	ST..	1D		YN501-YR328
0004	18		PA		4-9	33-21-12	D14594		D		GD03858	ST..	1D		YN501-YR328
0005	18		PA		3-8	33-21-12	D07177J	= 1	VY		SM00001		S		YN501-YR328
0006	18		PA		31-4	33-21-12	SM00001		S		SM00002		S		YN501
0006	18		PA		38-6	33-21-12	SM00001		S		SM00002		S		YR301-YR328
0007	18		PA		31-9	33-21-12	SM00002		S		SM00003		S		YN501
0007	18		PA		44-11	33-21-12	SM00002		S		SM00003		S		YR301-YR328
0011	18		PA		2-2	33-21-12	D14596		B		SM00001		S		YN501-YR328
0012	18		PA		4-9	33-21-12	D14596		C		GD03858	AC..	1D		YN501-YR328
0013	18		PA		4-9	33-21-12	D14596		A		GD03858	ST..	1D		YN501-YR328
0014	18		PA		4-9	33-21-12	D14596		D		GD03858	ST..	1D		YN501-YR328
0021	18		PA		3-0	33-21-12	D14598		B		SM00002		S		YN501
0021	18		PA		3-5	33-21-12	D14598		B		SM00002		S		YR301-YR328
0022	18		PA		2-7	33-21-12	D14598		C		GD03996	AC..	1		YN501
0022	18		PA		7-2	33-21-12	D14598		C		GD03798	AC..	1		YR301-YR328
0023	18		PA		2-7	33-21-12	D14598		A		GD03996	ST..	1		YN501
0023	18		PA		7-2	33-21-12	D14598		A		GD03798	ST..	1		YR301-YR328
0024	18		PA		1-7	33-21-12	D14598		D		SM00005		S		YN501
0024	18		PA		4-3	33-21-12	D14598		D		SM00005		S		YR301-YR328
0025	18		PA		1-7	33-21-12	SM00005		S		GD03996	ST..	1		YN501
0025	18		PA		5-3	33-21-12	SM00005		S		GD03798	ST..	1		YR301-YR328
0026	18		PA		2-0	33-21-12	SM00005		S		GD00205	ST..	E		YN501
0026	18		PA		3-2	33-21-12	SM00005		S		GD00217	ST..	E		YR301-YR328
0031	18		PA		3-0	33-21-12	D14600		B		SM00002		S		YN501
0031	18		PA		3-2	33-21-12	D14600		B		SM00002		S		YR301-YR328
0032	18		PA		2-7	33-21-12	D14600		C		GD03996	AC..	1		YN501
0032	18		PA		6-11	33-21-12	D14600		C		GD03798	AC..	1		YR301-YR328
0033	18		PA		2-7	33-21-12	D14600		A		GD03996	ST..	1		YN501
0033	18		PA		6-11	33-21-12	D14600		A		GD03798	ST..	1		YR301-YR328
0034	18		PA		1-7	33-21-12	D14600		D		SM00004		S		YN501
0034	18		PA		2-0	33-21-12	D14600		D		SM00004		S		YR301-YR328
0035	18		PA		1-7	33-21-12	SM00004		S		GD03996	ST..	1		YN501
0035	18		PA		6-0	33-21-12	SM00004		S		GD03798	ST..	1		YR301-YR328
0036	18		PA		1-5	33-21-12	SM00004		S		GD00207	ST..	E		YN501
0036	18		PA		3-11	33-21-12	SM00004		S		GD00207	ST..	E		YR301-YR328
0041	18		PA		2-8	33-21-12	D14602		B		SM00003		S		YN501
0041	18		PA		3-0	33-21-12	D14602		B		SM00003		S		YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4240

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4246		286A4246			LED LIGHTING - SIDEWALL RIGHT (continued)											
0042		18		PA		4-10	33-21-12	D14602		C		GD03816	AC..	1		YN501-YR328
0043		18		PA		4-10	33-21-12	D14602		A		GD03816	ST..	1		YN501-YR328
0044		18		PA		4-10	33-21-12	D14602		D		GD03816	ST..	1		YN501-YR328
0051		18		PA		2-8	33-21-12	D14604		B		SM00003		S		YN501
0051		18		PA		3-0	33-21-12	D14604		B		SM00003		S		YR301-YR328
0052		18		PA		4-10	33-21-12	D14604		C		GD03816	AC..	1		YN501-YR328
0053		18		PA		4-10	33-21-12	D14604		A		GD03816	ST..	1		YN501-YR328
0054		18		PA		4-10	33-21-12	D14604		D		GD03816	ST..	1		YN501-YR328
2001B		24		OT	EA	16-3	33-21-12	D14606		2		D41070J		2		YN501-YR328
2001W		24		OT	EA	0-0	33-21-12	D14606		1		D41070J		1		YN501-YR328
2001Z					EA	0-0	33-21-12	D14606		5		D41070J		5		YN501-YR328
2002B		24		PL	EB	16-3	33-21-12	D14606		4		D41070J		4		YN501-YR328
2002R		24		PL	EB	0-0	33-21-12	D14606		3		D41070J		3		YN501-YR328
2003B		24		OT	EC	20-2	33-24-22	D14608		2		D14656		2		YN501
2003B		24		OT	EC	19-9	33-24-22	D14608		2		D14656		2		YR301-YR328
2003W		24		OT	EC	0-0	33-24-22	D14608		1		D14656		1		YN501-YR328
2003Z					EC	0-0	33-24-22	D14608		5		D14656		5		YN501-YR328
2004B		24		PL	ED	20-2	33-24-22	D14608		4		D14656		4		YN501
2004B		24		PL	ED	19-9	33-24-22	D14608		4		D14656		4		YR301-YR328
2004R		24		PL	ED	0-0	33-24-22	D14608		3		D14656		3		YN501-YR328
W4248		286A4248			FLUORESCENT LIGHTING - RIGHT & LEFT - SIDEWALL											
0001		22		PA		10-4	33-21-12	D03796		1		SM00001		S		YC051-YL999
0001		22		PA		2-9	33-21-12	D03796		1		SM00001		S		YN231-YN260
0004		20		PA		3-9	33-21-12	D03796		4		SM00005		S		YC051-YL999
0004		20		PA		2-9	33-21-12	D03796		4		SM00005		S		YN231-YN260
0005		20		PA		7-2	33-21-12	D03796		5		GD03856	ST..	1		YC051-YN260
0006		20		PA		7-2	33-21-12	D03796		6		GD03856	AC..	1		YC051-YN260
0011		22		PA		10-5	33-21-12	D03798		1		SM00001		S		YC051-YL999
0011		22		PA		2-10	33-21-12	D03798		1		SM00001		S		YN231-YN260
0014		20		PA		3-10	33-21-12	D03798		4		SM00005		S		YC051-YL999
0014		20		PA		2-10	33-21-12	D03798		4		SM00005		S		YN231-YN260
0015		20		PA		7-3	33-21-12	D03798		5		GD03856	ST..	1		YC051-YN260
0016		20		PA		7-3	33-21-12	D03798		6		GD03856	AC..	1		YC051-YN260
0021		22		PA		13-8	33-21-12	D10014		1		SM00021		S		YC051-YL999
0021		22		PA		4-1	33-21-12	D03846		1		SM00021		S		YN231-YN260
0024		20		PA		6-2	33-21-12	D10014		4		SM00025		S		YC051-YL999
0024		20		PA		4-1	33-21-12	D03846		4		SM00025		S		YN231-YN260
0025		20		PA		5-4	33-21-12	D10014		5		GD03744	ST..	1		YC051-YL999

WIRE LIST

D280A108

91-21-11

Section W4240

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4248	286A4248				FLUORESCENT LIGHTING - RIGHT & LEFT - SIDEWALL (continued)											
0025	20		PA		2-6	33-21-12		D03846				GD03988	ST..	1		YN231-YN260
0026	20		PA		5-4	33-21-12		D10014				GD03744	AC..	1		YC051-YL999
0026	20		PA		2-6	33-21-12		D03846				GD03988	AC..	1		YN231-YN260
0031	22		PA		12-3	33-21-12		D10016				SM00021		S		YC051-YL999
0031	22		PA		4-6	33-21-12		D03848				SM00021		S		YN231-YN260
0034	20		PA		4-3	33-21-12		D10016				SM00025		S		YC051-YL999
0034	20		PA		4-6	33-21-12		D03848				SM00025		S		YN231-YN260
0035	20		PA		3-11	33-21-12		D10016				GD03744	ST..	1		YC051-YL999
0035	20		PA		2-11	33-21-12		D03848				GD03988	ST..	1		YN231-YN260
0036	20		PA		3-11	33-21-12		D10016				GD03744	AC..	1		YC051-YL999
0036	20		PA		2-11	33-21-12		D03848				GD03988	AC..	1		YN231-YN260
0041	22		PA		12-9	33-21-12		D03850				SM00041		S		YC051-YL999
0041	22		PA		2-4	33-21-12		D03850				SM00041		S		YN231-YN260
0044	20		PA		2-9	33-21-12		D03850				SM00045		S		YC051-YL999
0044	20		PA		2-4	33-21-12		D03850				SM00045		S		YN231-YN260
0045	20		PA		6-11	33-21-12		D03850				GD04006	ST..	1		YC051-YL999
0045	20		PA		6-3	33-21-12		D03850				GD04006	ST..	1		YN231-YN260
0046	20		PA		6-11	33-21-12		D03850				GD04006	AC..	1		YC051-YL999
0046	20		PA		6-3	33-21-12		D03850				GD04006	AC..	1		YN231-YN260
0051	22		PA		12-7	33-21-12		D03852				SM00041		S		YC051-YL999
0051	22		PA		2-6	33-21-12		D03852				SM00041		S		YN231-YN260
0054	20		PA		2-7	33-21-12		D03852				SM00045		S		YC051-YL999
0054	20		PA		2-6	33-21-12		D03852				SM00045		S		YN231-YN260
0055	20		PA		6-9	33-21-12		D03852				GD04006	ST..	1		YC051-YL999
0055	20		PA		6-5	33-21-12		D03852				GD04006	ST..	1		YN231-YN260
0056	20		PA		6-9	33-21-12		D03852				GD04006	AC..	1		YC051-YL999
0056	20		PA		6-5	33-21-12		D03852				GD04006	AC..	1		YN231-YN260
0101	22		PA		6-11	33-21-12		D03784				SM00001		S		YC051-YL999
0101	22		PA		12-10	33-21-12		D03784				SM00001		S		YN231-YN260
0104	20		PA		3-0	33-21-12		D03784				SM00004		S		YC051-YL999
0104	20		PA		2-10	33-21-12		D03784				SM00004		S		YN231-YN260
0105	20		PA		6-2	33-21-12		D03784				GD03858	ST..	1A		YC051-YN260
0106	20		PA		6-2	33-21-12		D03784				GD03858	AC..	1A		YC051-YN260
0111	22		PA		7-0	33-21-12		D03786				SM00001		S		YC051-YL999
0111	22		PA		12-8	33-21-12		D03786				SM00001		S		YN231-YN260
0114	20		PA		3-0	33-21-12		D03786				SM00004		S		YC051-YL999
0114	20		PA		2-8	33-21-12		D03786				SM00004		S		YN231-YN260
0115	20		PA		6-2	33-21-12		D03786				GD03858	ST..	1A		YC051-YL999
0115	20		PA		6-0	33-21-12		D03786				GD03858	ST..	1A		YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W4240

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4248		286A4248			FLUORESCENT LIGHTING - RIGHT & LEFT - SIDEWALL (continued)											
0116		20		PA		6-2	33-21-12	D03786				GD03858	AC..	1A		YC051-YL999
0116		20		PA		6-0	33-21-12	D03786				GD03858	AC..	1A		YN231-YN260
0121		22		PA		10-4	33-21-12	D10010				SM00021		S		YC051-YL999
0121		22		PA		11-8	33-21-12	D03788				SM00021		S		YN231-YN260
0124		20		PA		6-7	33-21-12	D10010				SM00024		S		YC051-YL999
0124		20		PA		3-4	33-21-12	D03788				SM00024		S		YN231-YN260
0125		20		PA		9-1	33-21-12	D10010				GD03798	ST..	1		YC051-YL999
0125		20		PA		2-11	33-21-12	D03788				GD03996	ST..	1		YN231-YN260
0126		20		PA		9-1	33-21-12	D10010				GD03798	AC..	1		YC051-YL999
0126		20		PA		2-11	33-21-12	D03788				GD03996	AC..	1		YN231-YN260
0131		22		PA		9-11	33-21-12	D10012				SM00021		S		YC051-YL999
0131		22		PA		12-1	33-21-12	D03790				SM00021		S		YN231-YN260
0134		20		PA		6-3	33-21-12	D10012				SM00024		S		YC051-YL999
0134		20		PA		3-8	33-21-12	D03790				SM00024		S		YN231-YN260
0135		20		PA		8-8	33-21-12	D10012				GD03798	ST..	1		YC051-YL999
0135		20		PA		3-3	33-21-12	D03790				GD03996	ST..	1		YN231-YN260
0136		20		PA		8-8	33-21-12	D10012				GD03798	AC..	1		YC051-YL999
0136		20		PA		3-3	33-21-12	D03790				GD03996	AC..	1		YN231-YN260
0141		22		PA		8-3	33-21-12	D03792				SM00041		S		YC051-YL999
0141		22		PA		13-3	33-21-12	D03792				SM00041		S		YN231-YN260
0144		20		PA		3-7	33-21-12	D03792				SM00044		S		YC051-YL999
0144		20		PA		3-0	33-21-12	D03792				SM00044		S		YN231-YN260
0145		20		PA		6-9	33-21-12	D03792				GD03816	ST..	1		YC051-YL999
0145		20		PA		6-0	33-21-12	D03792				GD03816	ST..	1		YN231-YN260
0146		20		PA		6-9	33-21-12	D03792				GD03816	AC..	1		YC051-YL999
0146		20		PA		6-0	33-21-12	D03792				GD03816	AC..	1		YN231-YN260
0151		22		PA		8-3	33-21-12	D03794				SM00041		S		YC051-YL999
0151		22		PA		13-4	33-21-12	D03794				SM00041		S		YN231-YN260
0154		20		PA		3-7	33-21-12	D03794				SM00044		S		YC051-YL999
0154		20		PA		3-0	33-21-12	D03794				SM00044		S		YN231-YN260
0155		20		PA		6-9	33-21-12	D03794				GD03816	ST..	1		YC051-YL999
0155		20		PA		6-1	33-21-12	D03794				GD03816	ST..	1		YN231-YN260
0156		20		PA		6-9	33-21-12	D03794				GD03816	AC..	1		YC051-YL999
0156		20		PA		6-1	33-21-12	D03794				GD03816	AC..	1		YN231-YN260
0201		22		PA		6-8	33-21-12	D07174P	= 1	VG		SM00001		S		YC051-YL999
0201		22		PA		4-0	33-21-12	D07174P	= 1	VG		SM00001		S		YN231-YN260
0304		20		PA		2-11	33-21-12	D40210J				SM00004		S		YC051-YL999
0304		20		PA		3-7	33-21-12	D40210J				SM00004		S		YN231-YN260
0305		20		PA		8-9	33-21-12	D40210J				SM00005		S		YC051-YL999

WIRE LIST

D280A108

91-21-11

Section W4240

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W4248	286A4248				FLUORESCENT LIGHTING - RIGHT & LEFT - SIDEWALL (continued)											
0305	20		PA		10-2	33-21-12	D40210J		1			SM00005		S		YN231-YN260
0321	22		PA		34-2	33-21-12	SM00001			S		SM00021		S		YC051-YL999
0321	22		PA		38-5	33-21-12	SM00001			S		SM00021		S		YN231-YN260
0324	20		PA		6-10	33-21-12	D40212J		2			SM00024		S		YC051-YL999
0324	20		PA		3-3	33-21-12	D40212J		2			SM00024		S		YN231-YN260
0325	20		PA		10-9	33-21-12	D40212J		1			SM00025		S		YC051-YL999
0325	20		PA		8-1	33-21-12	D40212J		1			SM00025		S		YN231-YN260
0341	22		PA		36-4	33-21-12	SM00021			S		SM00041		S		YC051-YL999
0341	22		PA		40-9	33-21-12	SM00021			S		SM00041		S		YN231-YN260
0344	20		PA		4-11	33-21-12	D40214J		2			SM00044		S		YC051-YL999
0344	20		PA		5-7	33-21-12	D40214J		2			SM00044		S		YN231-YN260
0345	20		PA		10-10	33-21-12	D40214J		1			SM00045		S		YC051-YL999
0345	20		PA		11-4	33-21-12	D40214J		1			SM00045		S		YN231-YN260

WIRE LIST
D280A108

91-21-11
Section W4240
Page 5 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S												
0001	16		CQ		3-3	35-21-31		SM00409		S		D07180J	= 1	VY		YC051-YL999, YR301-YR328	
0001	16		CQ		3-4	35-21-31		SM00409		S		D07180J	= 1	VY		YN231-YN501	
0101WY	18		PA		5-3	33-25-31		SM00501		S		SM00521		S		YC051-YL999, YR301-YR328	
0101WY	18		PA		2-3	33-25-31		SM00501		S		SM00521		S		YN231-YN501	
0102WV	22		PA		5-3	33-27-31		SM00502		S		SM00522		S		YC051-YL999, YR301-YR328	
0102WV	22		PA		2-3	33-27-31		SM00502		S		SM00522		S		YN231-YN501	
0103WG	22		PA		5-3	33-27-31		SM00503		S		SM00523		S		YC051-YL999, YR301-YR328	
0103WG	22		PA		2-3	33-27-31		SM00503		S		SM00523		S		YN231-YN501	
0104WO	22		PA		5-3	33-27-31		SM00504		S		SM00524		S		YC051-YL999, YR301-YR328	
0104WO	22		PA		2-3	33-27-31		SM00504		S		SM00524		S		YN231-YN501	
0105V	22		PA		5-3	33-27-31		SM00505		S		SM00525		S		YC051-YL999, YR301-YR328	
0105V	22		PA		2-3	33-27-31		SM00505		S		SM00525		S		YN231-YN501	
0106N	18		PA		5-3	33-23-21		SM00506		S		SM00526		S		YC051-YL999, YR301-YR328	
0106N	18		PA		2-3	33-23-21		SM00506		S		SM00526		S		YN231-YN501	
0107W	20		PA		5-3	33-25-31		SM00507		S		SM00527		S		YC051-YL999, YR301-YR328	
0107W	20		PA		2-3	33-25-31		SM00507		S		SM00527		S		YN231-YN501	
0108O	18		PA		5-3	33-23-21		SM00508		S		SM00528		S		YC051-YL999, YR301-YR328	
0108O	18		PA		2-3	33-23-21		SM00508		S		SM00528		S		YN231-YN501	
0109A	16		CQ		5-3	35-21-31		SM00509		S		SM00529		S		YC051-YL999, YR301-YR328	
0109A	16		CQ		2-3	35-21-31		SM00509		S		SM00529		S		YN231-YN501	
0110K	18		PA		5-3	33-27-31		SM00510		S		SM00530		S		YC051-YL999, YR301-YR328	
0110K	18		PA		2-3	33-27-31		SM00510		S		SM00530		S		YN231-YN501	
0121WY	18		PA		2-5	33-25-31		SM00521		S		SM00541		S		YC051-YL999, YR301-YR328	
0121WY	18		PA		3-9	33-25-31		SM00521		S		SM00541		S		YN231-YN501	
0122WV	22		PA		2-5	33-27-31		SM00522		S		SM00542		S		YC051-YL999, YR301-YR328	
0122WV	22		PA		3-9	33-27-31		SM00522		S		SM00542		S		YN231-YN501	

WIRE LIST

D280A108

91-21-11

Section W4250

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)										
0123WG	22		PA		2-5	33-27-31	SM00523		S		SM00543		S		YC051-YL999, YR301-YR328
0123WG	22		PA		3-9	33-27-31	SM00523		S		SM00543		S		YN231-YN501
0124WO	22		PA		2-5	33-27-31	SM00524		S		SM00544		S		YC051-YL999, YR301-YR328
0124WO	22		PA		3-9	33-27-31	SM00524		S		SM00544		S		YN231-YN501
0125V	22		PA		2-5	33-27-31	SM00525		S		SM00545		S		YC051-YL999, YR301-YR328
0125V	22		PA		3-9	33-27-31	SM00525		S		SM00545		S		YN231-YN501
0126N	18		PA		2-5	33-23-21	SM00526		S		SM00546		S		YC051-YL999, YR301-YR328
0126N	18		PA		3-9	33-23-21	SM00526		S		SM00546		S		YN231-YN501
0127W	20		PA		2-5	33-25-31	SM00527		S		SM00547		S		YC051-YL999, YR301-YR328
0127W	20		PA		3-9	33-25-31	SM00527		S		SM00547		S		YN231-YN501
0128O	18		PA		2-5	33-23-21	SM00528		S		SM00548		S		YC051-YL999, YR301-YR328
0128O	18		PA		3-9	33-23-21	SM00528		S		SM00548		S		YN231-YN501
0129A	16		CQ		2-5	35-21-31	SM00529		S		SM00549		S		YC051-YL999, YR301-YR328
0129A	16		CQ		3-9	35-21-31	SM00529		S		SM00549		S		YN231-YN501
0130K	18		PA		2-5	33-27-31	SM00530		S		SM00550		S		YC051-YL999, YR301-YR328
0130K	18		PA		3-9	33-27-31	SM00530		S		SM00550		S		YN231-YN501
0141WY	18		PA		6-1	33-25-31	SM00541		S		SM00561		S		YC051-YL999, YR301-YR328
0141WY	18		PA		5-4	33-25-31	SM00541		S		SM00561		S		YN231-YN501
0142WV	22		PA		6-1	33-27-31	SM00542		S		SM00562		S		YC051-YL999, YR301-YR328
0142WV	22		PA		5-4	33-27-31	SM00542		S		SM00562		S		YN231-YN501
0143WG	22		PA		6-1	33-27-31	SM00543		S		SM00563		S		YC051-YL999, YR301-YR328
0143WG	22		PA		5-4	33-27-31	SM00543		S		SM00563		S		YN231-YN501
0144WO	22		PA		6-1	33-27-31	SM00544		S		SM00564		S		YC051-YL999, YR301-YR328
0144WO	22		PA		5-4	33-27-31	SM00544		S		SM00564		S		YN231-YN501
0145V	22		PA		6-1	33-27-31	SM00545		S		SM00565		S		YC051-YL999, YR301-YR328
0145V	22		PA		5-4	33-27-31	SM00545		S		SM00565		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W4250

Page 2

Nov 12/2012

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250			P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
0147W	20		PA		6-1	33-25-31	SM00547		S		SM00567		S		YC051-YL999, YR301-YR328
0147W	20		PA		5-4	33-25-31	SM00547		S		SM00567		S		YN231-YN501
0149A	16		CQ		6-1	35-21-31	SM00549		S		SM00569		S		YC051-YL999, YR301-YR328
0149A	16		CQ		5-4	35-21-31	SM00549		S		SM00569		S		YN231-YN501
0150K	18		PA		6-1	33-27-31	SM00550		S		SM00570		S		YC051-YL999, YR301-YR328
0150K	18		PA		5-4	33-27-31	SM00550		S		SM00570		S		YN231-YN501
0161WY	18		PA		4-3	33-25-31	SM00561		S		SM00581		S		YC051-YL999, YR301-YR328
0161WY	18		PA		6-5	33-25-31	SM00561		S		SM00581		S		YN231-YN501
0162WV	22		PA		4-3	33-27-31	SM00562		S		SM00582		S		YC051-YL999, YR301-YR328
0162WV	22		PA		6-6	33-27-31	SM00562		S		SM00582		S		YN231-YN501
0163WG	22		PA		4-3	33-27-31	SM00563		S		SM00583		S		YC051-YL999, YR301-YR328
0163WG	22		PA		6-6	33-27-31	SM00563		S		SM00583		S		YN231-YN501
0164WO	22		PA		4-3	33-27-31	SM00564		S		SM00584		S		YC051-YL999, YR301-YR328
0164WO	22		PA		6-6	33-27-31	SM00564		S		SM00584		S		YN231-YN501
0165V	22		PA		4-3	33-27-31	SM00565		S		SM00585		S		YC051-YL999, YR301-YR328
0165V	22		PA		6-6	33-27-31	SM00565		S		SM00585		S		YN231-YN501
0166N	18		PA		4-3	33-23-21	SM00566		S		SM00586		S		YC051-YL999, YR301-YR328
0166N	18		PA		6-5	33-23-21	SM00566		S		SM00586		S		YN231-YN501
0167W	20		PA		4-3	33-25-31	SM00567		S		SM00587		S		YC051-YL999, YR301-YR328
0167W	20		PA		6-5	33-25-31	SM00567		S		SM00587		S		YN231-YN501
0168O	18		PA		4-3	33-23-21	SM00568		S		SM00588		S		YC051-YL999, YR301-YR328
0168O	18		PA		6-5	33-23-21	SM00568		S		SM00588		S		YN231-YN501
0169A	16		CQ		4-3	35-21-31	SM00569		S		SM00589		S		YC051-YL999, YR301-YR328
0169A	16		CQ		6-6	35-21-31	SM00569		S		SM00589		S		YN231-YN501
0170K	18		PA		4-3	33-27-31	SM00570		S		SM00590		S		YC051-YL999, YR301-YR328
0170K	18		PA		6-6	33-27-31	SM00570		S		SM00590		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W4250

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
0181WY	18		PA		4-1	33-25-31		SM00581		S		SM00601		S		YC051-YL999, YR301-YR328
0181WY	18		PA		7-2	33-25-31		SM00581		S		SM00641		S		YN231-YN501
0182WV	22		PA		4-1	33-27-31		SM00582		S		SM00602		S		YC051-YL999, YR301-YR328
0182WV	22		PA		7-2	33-27-31		SM00582		S		SM00642		S		YN231-YN501
0183WG	22		PA		4-1	33-27-31		SM00583		S		SM00603		S		YC051-YL999, YR301-YR328
0183WG	22		PA		7-2	33-27-31		SM00583		S		SM00643		S		YN231-YN501
0184WO	22		PA		4-1	33-27-31		SM00584		S		SM00604		S		YC051-YL999, YR301-YR328
0184WO	22		PA		7-2	33-27-31		SM00584		S		SM00644		S		YN231-YN501
0185V	22		PA		4-1	33-27-31		SM00585		S		SM00605		S		YC051-YL999, YR301-YR328
0185V	22		PA		7-2	33-27-31		SM00585		S		SM00645		S		YN231-YN501
0186N	18		PA		4-1	33-23-21		SM00586		S		SM00606		S		YC051-YL999, YR301-YR328
0187W	20		PA		4-1	33-25-31		SM00587		S		SM00607		S		YC051-YL999, YR301-YR328
0187W	20		PA		7-2	33-25-31		SM00587		S		SM00647		S		YN231-YN501
0188O	18		PA		4-1	33-23-21		SM00588		S		SM00608		S		YC051-YL999, YR301-YR328
0189A	16		CQ		4-1	35-21-31		SM00589		S		SM00609		S		YC051-YL999, YR301-YR328
0189A	16		CQ		7-2	35-21-31		SM00589		S		SM00649		S		YN231-YN501
0190K	18		PA		4-1	33-27-31		SM00590		S		SM00610		S		YC051-YL999, YR301-YR328
0190K	18		PA		7-2	33-27-31		SM00590		S		SM00650		S		YN231-YN501
0201WY	18		PA		4-2	33-25-31		SM00601		S		SM00621		S		YC051-YL999, YR301-YR328
0202WV	22		PA		4-2	33-27-31		SM00602		S		SM00622		S		YC051-YL999, YR301-YR328
0203WG	22		PA		4-2	33-27-31		SM00603		S		SM00623		S		YC051-YL999, YR301-YR328
0204WO	22		PA		4-2	33-27-31		SM00604		S		SM00624		S		YC051-YL999, YR301-YR328
0205V	22		PA		4-2	33-27-31		SM00605		S		SM00625		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250			P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
0207W	20		PA		4-2	33-25-31	SM00607		S		SM00627		S		YC051-YL999, YR301-YR328
0209A	16		CQ		4-2	35-21-31	SM00609		S		SM00629		S		YC051-YL999, YR301-YR328
0210K	18		PA		4-2	33-27-31	SM00610		S		SM00630		S		YC051-YL999, YR301-YR328
0221WY	18		PA		2-6	33-25-31	SM00621		S		SM00641		S		YC051-YL999, YR301-YR328
0222WV	22		PA		2-6	33-27-31	SM00622		S		SM00642		S		YC051-YL999, YR301-YR328
0223WG	22		PA		2-6	33-27-31	SM00623		S		SM00643		S		YC051-YL999, YR301-YR328
0224WO	22		PA		2-6	33-27-31	SM00624		S		SM00644		S		YC051-YL999, YR301-YR328
0225V	22		PA		2-6	33-27-31	SM00625		S		SM00645		S		YC051-YL999, YR301-YR328
0226N	18		PA		2-6	33-23-21	SM00626		S		SM00646		S		YC051-YL999, YR301-YR328
0227W	20		PA		2-6	33-25-31	SM00627		S		SM00647		S		YC051-YL999, YR301-YR328
0228O	18		PA		2-6	33-23-21	SM00628		S		SM00648		S		YC051-YL999, YR301-YR328
0229A	16		CQ		2-6	35-21-31	SM00629		S		SM00649		S		YC051-YL999, YR301-YR328
0230K	18		PA		2-6	33-27-31	SM00630		S		SM00650		S		YC051-YL999, YR301-YR328
0241WY	18		PA		6-8	33-25-31	SM00641		S		SM00661		S		YC051-YL999, YR301-YR328
0241WY	18		PA		6-3	33-25-31	SM00641		S		SM00661		S		YN231-YN501
0242WV	22		PA		6-8	33-27-31	SM00642		S		SM00662		S		YC051-YL999, YR301-YR328
0242WV	22		PA		6-3	33-27-31	SM00642		S		SM00662		S		YN231-YN501
0243WG	22		PA		6-8	33-27-31	SM00643		S		SM00663		S		YC051-YL999, YR301-YR328
0243WG	22		PA		6-3	33-27-31	SM00643		S		SM00663		S		YN231-YN501
0244WO	22		PA		6-8	33-27-31	SM00644		S		SM00664		S		YC051-YL999, YR301-YR328
0244WO	22		PA		6-3	33-27-31	SM00644		S		SM00664		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W4250

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)										
0245V	22		PA		6-8	33-27-31	SM00645		S		SM00665		S		YC051-YL999, YR301-YR328
0245V	22		PA		6-3	33-27-31	SM00645		S		SM00665		S		YN231-YN501
0246N	18		PA		6-8	33-23-21	SM00646		S		SM00666		S		YC051-YL999, YR301-YR328
0247W	20		PA		6-8	33-25-31	SM00647		S		SM00667		S		YC051-YL999, YR301-YR328
0247W	20		PA		6-3	33-25-31	SM00647		S		SM00667		S		YN231-YN501
0248O	18		PA		6-8	33-23-21	SM00648		S		SM00668		S		YC051-YL999, YR301-YR328
0249A	16		CQ		6-8	35-21-31	SM00649		S		SM00669		S		YC051-YL999, YR301-YR328
0249A	16		CQ		6-3	35-21-31	SM00649		S		SM00669		S		YN231-YN501
0250K	18		PA		6-8	33-27-31	SM00650		S		SM00670		S		YC051-YL999, YR301-YR328
0250K	18		PA		6-3	33-27-31	SM00650		S		SM00670		S		YN231-YN501
0261WY	18		PA		3-8	33-25-31	SM00661		S		SM00681		S		YC051-YL999, YR301-YR328
0261WY	18		PA		4-5	33-25-31	SM00661		S		SM00681		S		YN231-YN501
0262WV	22		PA		3-8	33-27-31	SM00662		S		SM00682		S		YC051-YL999, YR301-YR328
0262WV	22		PA		4-5	33-27-32	SM00662		S		SM00682		S		YN231-YN501
0263WG	22		PA		3-8	33-27-31	SM00663		S		SM00683		S		YC051-YL999, YR301-YR328
0263WG	22		PA		4-5	33-27-32	SM00663		S		SM00683		S		YN231-YN501
0264WO	22		PA		3-8	33-27-31	SM00664		S		SM00684		S		YC051-YL999, YR301-YR328
0264WO	22		PA		4-5	33-27-32	SM00664		S		SM00684		S		YN231-YN501
0265V	22		PA		3-8	33-27-31	SM00665		S		SM00685		S		YC051-YL999, YR301-YR328
0265V	22		PA		4-5	33-27-32	SM00665		S		SM00685		S		YN231-YN501
0266N	18		PA		4-5	33-23-21	SM00666		S		SM00686		S		YN231-YN501
0267W	20		PA		3-8	33-25-31	SM00667		S		SM00687		S		YC051-YL999, YR301-YR328
0267W	20		PA		4-5	33-25-31	SM00667		S		SM00687		S		YN231-YN501
0268O	18		PA		4-5	33-23-21	SM00668		S		SM00688		S		YN231-YN501
0269A	16		CQ		3-8	35-21-31	SM00669		S		SM00689		S		YC051-YL999, YR301-YR328
0269A	16		CQ		4-5	35-21-31	SM00669		S		SM00689		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W4250

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)												
0270K	18		PA		3-8		33-27-31	SM00670		S		SM00690		S		YC051-YL999, YR301-YR328	
0270K	18		PA		4-5		33-27-32	SM00670		S		SM00690		S		YN231-YN501	
0281WY	18		PA		5-1		33-25-31	SM00681		S		SM00701		S		YC051-YL999, YR301-YR328	
0282WV	22		PA		5-1		33-27-31	SM00682		S		SM00702		S		YC051-YL999, YR301-YR328	
0282WV	22		PA		6-6		33-27-32	SM00682		S		SM00702		S		YN231-YN501	
0283WG	22		PA		5-1		33-27-31	SM00683		S		SM00703		S		YC051-YL999, YR301-YR328	
0283WG	22		PA		6-6		33-27-32	SM00683		S		SM00703		S		YN231-YN501	
0284WO	22		PA		5-1		33-27-31	SM00684		S		SM00704		S		YC051-YL999, YR301-YR328	
0284WO	22		PA		6-6		33-27-32	SM00684		S		SM00704		S		YN231-YN501	
0285V	22		PA		5-1		33-27-31	SM00685		S		SM00705		S		YC051-YL999, YR301-YR328	
0285V	22		PA		6-6		33-27-32	SM00685		S		SM00705		S		YN231-YN501	
0286N	18		PA		5-1		33-23-21	SM00686		S		SM00706		S		YC051-YL999, YR301-YR328	
0287W	20		PA		5-1		33-25-31	SM00687		S		SM00707		S		YC051-YL999, YR301-YR328	
0288O	18		PA		5-1		33-23-21	SM00688		S		SM00708		S		YC051-YL999, YR301-YR328	
0289A	16		CQ		5-1		35-21-31	SM00689		S		SM00709		S		YC051-YL999, YR301-YR328	
0290K	18		PA		5-1		33-27-31	SM00690		S		SM00710		S		YC051-YL999, YR301-YR328	
0290K	18		PA		6-6		33-27-32	SM00690		S		SM00710		S		YN231-YN501	
0301WY	18		PA		2-8		33-25-31	SM00701		S		SM00721		S		YC051-YL999, YR301-YR328	
0301WY	18		PA		6-0		33-25-32	SM00701		S		SM00721		S		YN231-YN501	
0302WV	22		PA		2-8		33-27-31	SM00702		S		SM00722		S		YC051-YL999, YR301-YR328	
0302WV	22		PA		6-0		33-27-32	SM00702		S		SM00722		S		YN231-YN501	
0303WG	22		PA		2-8		33-27-31	SM00703		S		SM00723		S		YC051-YL999, YR301-YR328	
0303WG	22		PA		6-0		33-27-32	SM00703		S		SM00723		S		YN231-YN501	
0304WO	22		PA		2-8		33-27-31	SM00704		S		SM00724		S		YC051-YL999, YR301-YR328	

WIRE LIST

D280A108

91-21-11

Section W4250

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)										
0304WO	22		PA		6-0	33-27-32	SM00704				SM00724		S		YN231-YN501
0305V	22		PA		2-8	33-27-31	SM00705				SM00725		S		YC051-YL999, YR301-YR328
0305V	22		PA		6-0	33-27-32	SM00705				SM00725		S		YN231-YN501
0306N	18		PA		2-8	33-23-21	SM00706				SM00726		S		YC051-YL999, YR301-YR328
0306N	18		PA		6-0	33-23-22	SM00706				SM00726		S		YN231-YN501
0307W	20		PA		2-8	33-25-31	SM00707				SM00727		S		YC051-YL999, YR301-YR328
0307W	20		PA		6-0	33-25-32	SM00707				SM00727		S		YN231-YN501
0308O	18		PA		2-8	33-23-21	SM00708				SM00728		S		YC051-YL999, YR301-YR328
0308O	18		PA		6-0	33-23-22	SM00708				SM00728		S		YN231-YN501
0309A	16		CQ		2-8	35-21-31	SM00709				SM00729		S		YC051-YL999, YR301-YR328
0309A	16		CQ		6-0	35-21-31	SM00709				SM00729		S		YN231-YN501
0310K	18		PA		2-8	33-27-31	SM00710				SM00730		S		YC051-YL999, YR301-YR328
0310K	18		PA		6-0	33-27-32	SM00710				SM00730		S		YN231-YN501
0321WY	18		PA		6-1	33-25-32	SM00721				SM00741		S		YN231-YN501
0322WV	22		PA		6-6	33-27-32	SM00722				SM00742		S		YC051-YL999, YR301-YR328
0322WV	22		PA		6-1	33-27-32	SM00722				SM00742		S		YN231-YN501
0323WG	22		PA		6-6	33-27-32	SM00723				SM00743		S		YC051-YL999, YR301-YR328
0323WG	22		PA		6-1	33-27-32	SM00723				SM00743		S		YN231-YN501
0324WO	22		PA		6-6	33-27-32	SM00724				SM00744		S		YC051-YL999, YR301-YR328
0324WO	22		PA		6-1	33-27-32	SM00724				SM00744		S		YN231-YN501
0325V	22		PA		6-6	33-27-32	SM00725				SM00745		S		YC051-YL999, YR301-YR328
0325V	22		PA		6-1	33-27-32	SM00725				SM00745		S		YN231-YN501
0327W	20		PA		6-1	33-25-32	SM00727				SM00747		S		YN231-YN501
0329A	16		CQ		6-1	35-21-31	SM00729				SM00749		S		YN231-YN501
0330K	18		PA		6-6	33-27-32	SM00730				SM00750		S		YC051-YL999, YR301-YR328
0330K	18		PA		6-1	33-27-32	SM00730				SM00750		S		YN231-YN501
0341WY	18		PA		4-0	33-25-32	SM00741				SM00761		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)												
0341WY	18		PA		3-11	33-25-32		SM00741		S		SM00821		S		YN231-YN501	
0342WV	22		PA		4-0	33-27-32		SM00742		S		SM00762		S		YC051-YL999, YR301-YR328	
0342WV	22		PA		3-11	33-27-32		SM00742		S		SM00822		S		YN231-YN501	
0343WG	22		PA		4-0	33-27-32		SM00743		S		SM00763		S		YC051-YL999, YR301-YR328	
0343WG	22		PA		3-11	33-27-32		SM00743		S		SM00823		S		YN231-YN501	
0344WO	22		PA		4-0	33-27-32		SM00744		S		SM00764		S		YC051-YL999, YR301-YR328	
0344WO	22		PA		3-11	33-27-32		SM00744		S		SM00824		S		YN231-YN501	
0345V	22		PA		4-0	33-27-32		SM00745		S		SM00765		S		YC051-YL999, YR301-YR328	
0345V	22		PA		3-11	33-27-32		SM00745		S		SM00825		S		YN231-YN501	
0346N	18		PA		4-0	33-23-22		SM00746		S		SM00766		S		YC051-YL999, YR301-YR328	
0346N	18		PA		3-11	33-23-22		SM00746		S		SM00826		S		YN231-YN501	
0347W	20		PA		4-0	33-25-32		SM00747		S		SM00767		S		YC051-YL999, YR301-YR328	
0347W	20		PA		3-11	33-25-32		SM00747		S		SM00827		S		YN231-YN501	
0348O	18		PA		4-0	33-23-22		SM00748		S		SM00768		S		YC051-YL999, YR301-YR328	
0348O	18		PA		3-11	33-23-22		SM00748		S		SM00828		S		YN231-YN501	
0349A	16		CQ		4-0	35-21-31		SM00749		S		SM00769		S		YC051-YL999, YR301-YR328	
0349A	16		CQ		3-11	35-21-31		SM00749		S		SM00829		S		YN231-YN501	
0350K	18		PA		4-0	33-27-32		SM00750		S		SM00770		S		YC051-YL999, YR301-YR328	
0350K	18		PA		3-11	33-27-32		SM00750		S		SM00830		S		YN231-YN501	
0361WY	18		PA		3-11	33-25-32		SM00761		S		SM00781		S		YC051-YL999, YR301-YR328	
0362WV	22		PA		3-11	33-27-32		SM00762		S		SM00782		S		YC051-YL999, YR301-YR328	
0363WG	22		PA		3-11	33-27-32		SM00763		S		SM00783		S		YC051-YL999, YR301-YR328	
0364WO	22		PA		3-11	33-27-32		SM00764		S		SM00784		S		YC051-YL999, YR301-YR328	
0365V	22		PA		3-11	33-27-32		SM00765		S		SM00785		S		YC051-YL999, YR301-YR328	

WIRE LIST

D280A108

91-21-11

Section W4250

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250			P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
0366N	18		PA		3-11	33-23-22	SM00766				SM00786		S		YC051-YL999, YR301-YR328
0367W	20		PA		3-11	33-25-32	SM00767				SM00787		S		YC051-YL999, YR301-YR328
0368O	18		PA		3-11	33-23-22	SM00768				SM00788		S		YC051-YL999, YR301-YR328
0369A	16		CQ		3-11	35-21-31	SM00769				SM00789		S		YC051-YL999, YR301-YR328
0370K	18		PA		3-11	33-27-32	SM00770				SM00790		S		YC051-YL999, YR301-YR328
0381WY	18		PA		4-5	33-25-32	SM00781				SM00801		S		YC051-YL999, YR301-YR328
0382WV	22		PA		4-5	33-27-32	SM00782				SM00802		S		YC051-YL999, YR301-YR328
0383WG	22		PA		4-5	33-27-32	SM00783				SM00803		S		YC051-YL999, YR301-YR328
0384WO	22		PA		4-5	33-27-32	SM00784				SM00804		S		YC051-YL999, YR301-YR328
0385V	22		PA		4-5	33-27-32	SM00785				SM00805		S		YC051-YL999, YR301-YR328
0387W	20		PA		4-5	33-25-32	SM00787				SM00807		S		YC051-YL999, YR301-YR328
0389A	16		CQ		4-5	35-21-31	SM00789				SM00809		S		YC051-YL999, YR301-YR328
0390K	18		PA		4-5	33-27-32	SM00790				SM00810		S		YC051-YL999, YR301-YR328
0401WY	18		PA		4-1	33-25-32	SM00801				SM00821		S		YC051-YL999, YR301-YR328
0402WV	22		PA		4-1	33-27-32	SM00802				SM00822		S		YC051-YL999, YR301-YR328
0403WG	22		PA		4-1	33-27-32	SM00803				SM00823		S		YC051-YL999, YR301-YR328
0404WO	22		PA		4-1	33-27-32	SM00804				SM00824		S		YC051-YL999, YR301-YR328
0405V	22		PA		4-1	33-27-32	SM00805				SM00825		S		YC051-YL999, YR301-YR328
0406N	18		PA		4-1	33-23-22	SM00806				SM00826		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 10

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From				To					
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
0407W	20		PA		4-1	33-25-32	SM00807			S		SM00827		S		YC051-YL999, YR301-YR328
0408O	18		PA		4-1	33-23-22	SM00808			S		SM00828		S		YC051-YL999, YR301-YR328
0409A	16		CQ		4-1	35-21-31	SM00809			S		SM00829		S		YC051-YL999, YR301-YR328
0410K	18		PA		4-1	33-27-32	SM00810			S		SM00830		S		YC051-YL999, YR301-YR328
0421WY	18		PA		4-2	33-25-32	SM00821			S		SM00841		S		YC051-YL999, YR301-YR328
0421WY	18		PA		3-3	33-25-32	SM00821			S		SM00841		S		YN231-YN501
0422WV	22		PA		4-2	33-27-32	SM00822			S		SM00842		S		YC051-YL999, YR301-YR328
0422WV	22		PA		3-3	33-27-32	SM00822			S		SM00842		S		YN231-YN501
0423WG	22		PA		4-2	33-27-32	SM00823			S		SM00843		S		YC051-YL999, YR301-YR328
0423WG	22		PA		3-3	33-27-32	SM00823			S		SM00843		S		YN231-YN501
0424WO	22		PA		4-2	33-27-32	SM00824			S		SM00844		S		YC051-YL999, YR301-YR328
0424WO	22		PA		3-3	33-27-32	SM00824			S		SM00844		S		YN231-YN501
0425V	22		PA		4-2	33-27-32	SM00825			S		SM00845		S		YC051-YL999, YR301-YR328
0425V	22		PA		3-3	33-27-32	SM00825			S		SM00845		S		YN231-YN501
0427W	20		PA		4-2	33-25-32	SM00827			S		SM00847		S		YC051-YL999, YR301-YR328
0427W	20		PA		3-3	33-25-32	SM00827			S		SM00847		S		YN231-YN501
0429A	16		CQ		4-2	35-21-31	SM00829			S		SM00849		S		YC051-YL999, YR301-YR328
0429A	16		CQ		3-3	35-21-31	SM00829			S		SM00849		S		YN231-YN501
0430K	18		PA		4-2	33-27-32	SM00830			S		SM00850		S		YC051-YL999, YR301-YR328
0430K	18		PA		3-3	33-27-32	SM00830			S		SM00850		S		YN231-YN501
0441WY	18		PA		4-0	33-25-32	SM00841			S		SM00861		S		YC051-YL999, YR301-YR328
0441WY	18		PA		8-1	33-25-32	SM00841			S		SM00861		S		YN231-YN501
0442WV	22		PA		4-0	33-27-32	SM00842			S		SM00862		S		YC051-YL999, YR301-YR328
0442WV	22		PA		8-1	33-27-32	SM00842			S		SM00862		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W4250

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
0443WG	22		PA		4-0	33-27-32		SM00843		S		SM00863		S		YC051-YL999, YR301-YR328
0443WG	22		PA		8-1	33-27-32		SM00843		S		SM00863		S		YN231-YN501
0444WO	22		PA		4-0	33-27-32		SM00844		S		SM00864		S		YC051-YL999, YR301-YR328
0444WO	22		PA		8-1	33-27-32		SM00844		S		SM00864		S		YN231-YN501
0445V	22		PA		4-0	33-27-32		SM00845		S		SM00865		S		YC051-YL999, YR301-YR328
0445V	22		PA		8-1	33-27-32		SM00845		S		SM00865		S		YN231-YN501
0446N	18		PA		4-0	33-23-22		SM00846		S		SM00866		S		YC051-YL999, YR301-YR328
0446N	18		PA		8-1	33-23-22		SM00846		S		SM00866		S		YN231-YN501
0447W	20		PA		4-0	33-25-32		SM00847		S		SM00867		S		YC051-YL999, YR301-YR328
0447W	20		PA		8-1	33-25-32		SM00847		S		SM00867		S		YN231-YN501
0448O	18		PA		4-0	33-23-22		SM00848		S		SM00868		S		YC051-YL999, YR301-YR328
0448O	18		PA		8-1	33-23-22		SM00848		S		SM00868		S		YN231-YN501
0449A	16		CQ		4-0	35-21-31		SM00849		S		SM00869		S		YC051-YL999, YR301-YR328
0449A	16		CQ		8-1	35-21-31		SM00849		S		SM00869		S		YN231-YN501
0450K	18		PA		4-0	33-27-32		SM00850		S		SM00870		S		YC051-YL999, YR301-YR328
0450K	18		PA		8-1	33-27-32		SM00850		S		SM00870		S		YN231-YN501
0461WY	18		PA		3-10	33-25-32		SM00861		S		SM00881		S		YC051-YL999, YR301-YR328
0462WV	22		PA		3-10	33-27-32		SM00862		S		SM00882		S		YC051-YL999, YR301-YR328
0463WG	22		PA		3-10	33-27-32		SM00863		S		SM00883		S		YC051-YL999, YR301-YR328
0464WO	22		PA		3-10	33-27-32		SM00864		S		SM00884		S		YC051-YL999, YR301-YR328
0465V	22		PA		3-10	33-27-32		SM00865		S		SM00885		S		YC051-YL999, YR301-YR328
0467W	20		PA		3-10	33-25-32		SM00867		S		SM00887		S		YC051-YL999, YR301-YR328
0469A	16		CQ		3-10	35-21-31		SM00869		S		SM00889		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)												
0470K	18		PA		3-10		33-27-32	SM00870		S		SM00890		S		YC051-YL999, YR301-YR328	
0481WY	18		PA		2-4		33-25-32	SM00881		S		SM00901		S		YC051-YL999, YR301-YR328	
0482WV	22		PA		2-4		33-27-32	SM00882		S		SM00902		S		YC051-YL999, YR301-YR328	
0483WG	22		PA		2-4		33-27-32	SM00883		S		SM00903		S		YC051-YL999, YR301-YR328	
0484WO	22		PA		2-4		33-27-32	SM00884		S		SM00904		S		YC051-YL999, YR301-YR328	
0485V	22		PA		2-4		33-27-32	SM00885		S		SM00905		S		YC051-YL999, YR301-YR328	
0486N	18		PA		2-4		33-23-22	SM00886		S		SM00906		S		YC051-YL999, YR301-YR328	
0487W	20		PA		2-4		33-25-32	SM00887		S		SM00907		S		YC051-YL999, YR301-YR328	
0488O	18		PA		2-4		33-23-22	SM00888		S		SM00908		S		YC051-YL999, YR301-YR328	
0489A	16		CQ		2-4		35-21-31	SM00889		S		SM00909		S		YC051-YL999, YR301-YR328	
0490K	18		PA		2-4		33-27-32	SM00890		S		SM00910		S		YC051-YL999, YR301-YR328	
0491WY	18		PA		8-7		33-25-31	D11600		1		SM00501		S		YC051-YL999, YR301-YR328	
0491WY	18		PA		6-11		33-25-31	D11600		1		SM00501		S		YN231-YN501	
0492WV	22		PA		8-7		33-27-31	D11600		2		SM00502		S		YC051-YL999, YR301-YR328	
0492WV	22		PA		7-2		33-27-31	D11600		2		SM00502		S		YN231-YN501	
0493WG	22		PA		8-7		33-27-31	D11600		3		SM00503		S		YC051-YL999, YR301-YR328	
0493WG	22		PA		7-2		33-27-31	D11600		3		SM00503		S		YN231-YN501	
0494WO	22		PA		8-7		33-27-31	D11600		4		SM00504		S		YC051-YL999, YR301-YR328	
0494WO	22		PA		7-2		33-27-31	D11600		4		SM00504		S		YN231-YN501	
0495V	22		PA		8-7		33-27-31	D11600		5		SM00505		S		YC051-YL999, YR301-YR328	
0495V	22		PA		7-2		33-27-31	D11600		5		SM00505		S		YN231-YN501	
0496N	18		PA		8-7		33-23-21	D11600		6		SM00506		S		YC051-YL999, YR301-YR328	

WIRE LIST

D280A108

91-21-11

Section W4250

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)										
0496N	18		PA		6-11	33-23-21	D11600				SM00506		S		YN231-YN501
0497W	20		PA		8-7	33-25-31	D11600				SM00507		S		YC051-YL999, YR301-YR328
0497W	20		PA		6-11	33-25-31	D11600				SM00507		S		YN231-YN501
0498O	18		PA		8-7	33-23-21	D11600				SM00508		S		YC051-YL999, YR301-YR328
0498O	18		PA		6-11	33-23-21	D11600				SM00508		S		YN231-YN501
0499A	16		CQ		8-7	35-21-31	D11600				SM00509		S		YC051-YL999, YR301-YR328
0499A	16		CQ		7-2	35-21-31	D11600				SM00509		S		YN231-YN501
0500K	18		PA		8-7	33-27-31	D11600				SM00510		S		YC051-YL999, YR301-YR328
0500K	18		PA		7-2	33-27-31	D11600				SM00510		S		YN231-YN501
0501WY	18		PA		9-10	33-25-31	D11602				SM00501		S		YC051-YL999, YR301-YR328
0501WY	18		PA		10-0	33-25-31	D11602				SM00501		S		YN231-YN501
0502WV	22		PA		9-10	33-27-31	D11602				SM00502		S		YC051-YL999, YR301-YR328
0502WV	22		PA		10-1	33-27-31	D11602				SM00502		S		YN231-YN501
0503WG	22		PA		9-10	33-27-31	D11602				SM00503		S		YC051-YL999, YR301-YR328
0503WG	22		PA		10-1	33-27-31	D11602				SM00503		S		YN231-YN501
0504WO	22		PA		9-10	33-27-31	D11602				SM00504		S		YC051-YL999, YR301-YR328
0504WO	22		PA		10-1	33-27-31	D11602				SM00504		S		YN231-YN501
0505V	22		PA		9-10	33-27-31	D11602				SM00505		S		YC051-YL999, YR301-YR328
0505V	22		PA		10-1	33-27-31	D11602				SM00505		S		YN231-YN501
0506N	18		PA		9-10	33-23-21	D11602				SM00506		S		YC051-YL999, YR301-YR328
0506N	18		PA		10-0	33-23-21	D11602				SM00506		S		YN231-YN501
0507W	20		PA		9-10	33-25-31	D11602				SM00507		S		YC051-YL999, YR301-YR328
0507W	20		PA		10-0	33-25-31	D11602				SM00507		S		YN231-YN501
0508O	18		PA		9-10	33-23-21	D11602				SM00508		S		YC051-YL999, YR301-YR328
0508O	18		PA		10-0	33-23-21	D11602				SM00508		S		YN231-YN501
0509A	16		CQ		9-10	35-21-31	D11602				SM00509		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To			Effectivity				
Wire No.	GA	CO TY	Fam		FT-IN	Diagram	Equip	Term	Type	Splice		Equip	Term	Type	Splice
W4250	286A4250			P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
0509A	16	CQ		10-1	35-21-31	D11602		11			SM00509		S		YN231-YN501
0510K	18	PA		9-10	33-27-31	D11602		10			SM00510		S		YC051-YL999, YR301-YR328
0510K	18	PA		10-1	33-27-31	D11602		10			SM00510		S		YN231-YN501
0511WY	18	PA		9-7	33-25-31	D11604		1			SM00521		S		YC051-YL999
0511WY	18	PA		8-11	33-25-31	D11604		1			SM00521		S		YN231-YN501
0511WY	18	PA		9-5	33-25-31	D11604		1			SM00521		S		YR301-YR328
0512WV	22	PA		9-7	33-27-31	D11604		2			SM00522		S		YC051-YL999
0512WV	22	PA		9-0	33-27-31	D11604		2			SM00522		S		YN231-YN501
0512WV	22	PA		9-5	33-27-31	D11604		2			SM00522		S		YR301-YR328
0513WG	22	PA		9-7	33-27-31	D11604		3			SM00523		S		YC051-YL999
0513WG	22	PA		9-0	33-27-31	D11604		3			SM00523		S		YN231-YN501
0513WG	22	PA		9-5	33-27-31	D11604		3			SM00523		S		YR301-YR328
0514WO	22	PA		9-7	33-27-31	D11604		4			SM00524		S		YC051-YL999
0514WO	22	PA		9-0	33-27-31	D11604		4			SM00524		S		YN231-YN501
0514WO	22	PA		9-5	33-27-31	D11604		4			SM00524		S		YR301-YR328
0515V	22	PA		9-7	33-27-31	D11604		5			SM00525		S		YC051-YL999
0515V	22	PA		9-0	33-27-31	D11604		5			SM00525		S		YN231-YN501
0515V	22	PA		9-5	33-27-31	D11604		5			SM00525		S		YR301-YR328
0516N	18	PA		9-7	33-23-21	D11604		6			SM00526		S		YC051-YL999
0516N	18	PA		8-11	33-23-21	D11604		6			SM00526		S		YN231-YN501
0516N	18	PA		9-5	33-23-21	D11604		6			SM00526		S		YR301-YR328
0517W	20	PA		9-7	33-25-31	D11604		7			SM00527		S		YC051-YL999
0517W	20	PA		8-11	33-25-31	D11604		7			SM00527		S		YN231-YN501
0517W	20	PA		9-5	33-25-31	D11604		7			SM00527		S		YR301-YR328
0518O	18	PA		9-7	33-23-21	D11604		8			SM00528		S		YC051-YL999
0518O	18	PA		8-11	33-23-21	D11604		8			SM00528		S		YN231-YN501
0518O	18	PA		9-5	33-23-21	D11604		8			SM00528		S		YR301-YR328
0519A	16	CQ		9-7	35-21-31	D11604		11			SM00529		S		YC051-YL999
0519A	16	CQ		9-0	35-21-31	D11604		11			SM00529		S		YN231-YN501
0519A	16	CQ		9-5	35-21-31	D11604		11			SM00529		S		YR301-YR328
0520K	18	PA		9-7	33-27-31	D11604		10			SM00530		S		YC051-YL999
0520K	18	PA		9-0	33-27-31	D11604		10			SM00530		S		YN231-YN501
0520K	18	PA		9-5	33-27-31	D11604		10			SM00530		S		YR301-YR328
0521WY	18	PA		7-3	33-25-31	D11606		1			SM00521		S		YC051-YL999, YR301-YR328
0521WY	18	PA		6-11	33-25-31	D11606		1			SM00521		S		YN231-YN501
0522WV	22	PA		7-3	33-27-31	D11606		2			SM00522		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity			
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice	
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
0522WV	22		PA		6-11	33-27-31	D11606		2		SM00522		S		YN231-YN501	
0523WG	22		PA		7-3	33-27-31	D11606		3		SM00523		S		YC051-YL999, YR301-YR328	
0523WG	22		PA		6-11	33-27-31	D11606		3		SM00523		S		YN231-YN501	
0524WO	22		PA		7-3	33-27-31	D11606		4		SM00524		S		YC051-YL999, YR301-YR328	
0524WO	22		PA		6-11	33-27-31	D11606		4		SM00524		S		YN231-YN501	
0525V	22		PA		7-3	33-27-31	D11606		5		SM00525		S		YC051-YL999, YR301-YR328	
0525V	22		PA		6-11	33-27-31	D11606		5		SM00525		S		YN231-YN501	
0526N	18		PA		7-3	33-23-21	D11606		6		SM00526		S		YC051-YL999, YR301-YR328	
0526N	18		PA		6-11	33-23-21	D11606		6		SM00526		S		YN231-YN501	
0527W	20		PA		7-3	33-25-31	D11606		7		SM00527		S		YC051-YL999, YR301-YR328	
0527W	20		PA		6-11	33-25-31	D11606		7		SM00527		S		YN231-YN501	
0528O	18		PA		7-3	33-23-21	D11606		8		SM00528		S		YC051-YL999, YR301-YR328	
0528O	18		PA		6-11	33-23-21	D11606		8		SM00528		S		YN231-YN501	
0529A	16		CQ		7-3	35-21-31	D11606		11		SM00529		S		YC051-YL999, YR301-YR328	
0529A	16		CQ		6-11	35-21-31	D11606		11		SM00529		S		YN231-YN501	
0530K	18		PA		7-3	33-27-31	D11606		10		SM00530		S		YC051-YL999, YR301-YR328	
0530K	18		PA		6-11	33-27-31	D11606		10		SM00530		S		YN231-YN501	
0531WY	18		PA		7-7	33-25-31	D11608		1		SM00541		S		YC051-YL999, YR301-YR328	
0531WY	18		PA		6-11	33-25-31	D11608		1		SM00541		S		YN231-YN501	
0532WV	22		PA		7-7	33-27-31	D11608		2		SM00542		S		YC051-YL999, YR301-YR328	
0532WV	22		PA		7-0	33-27-31	D11608		2		SM00542		S		YN231-YN501	
0533WG	22		PA		7-7	33-27-31	D11608		3		SM00543		S		YC051-YL999, YR301-YR328	
0533WG	22		PA		7-0	33-27-31	D11608		3		SM00543		S		YN231-YN501	
0534WO	22		PA		7-7	33-27-31	D11608		4		SM00544		S		YC051-YL999, YR301-YR328	
0534WO	22		PA		7-0	33-27-31	D11608		4		SM00544		S		YN231-YN501	
0535V	22		PA		7-7	33-27-31	D11608		5		SM00545		S		YC051-YL999, YR301-YR328	

WIRE LIST

D280A108

91-21-11

Section W4250

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
0535V	22		PA		7-0	33-27-31	D11608		5			SM00545		S		YN231-YN501
0536N	18		PA		7-7	33-23-21	D11608		6			SM00546		S		YC051-YL999, YR301-YR328
0536N	18		PA		6-11	33-23-21	D11608		6			SM00546		S		YN231-YN501
0537W	20		PA		7-7	33-25-31	D11608		7			SM00547		S		YC051-YL999, YR301-YR328
0537W	20		PA		6-11	33-25-31	D11608		7			SM00547		S		YN231-YN501
0538O	18		PA		7-7	33-23-21	D11608		8			SM00548		S		YC051-YL999, YR301-YR328
0538O	18		PA		6-11	33-23-21	D11608		8			SM00548		S		YN231-YN501
0539A	16		CQ		7-7	35-21-31	D11608		11			SM00549		S		YC051-YL999, YR301-YR328
0539A	16		CQ		7-0	35-21-31	D11608		11			SM00549		S		YN231-YN501
0540K	18		PA		7-7	33-27-31	D11608		10			SM00550		S		YC051-YL999, YR301-YR328
0540K	18		PA		7-0	33-27-31	D11608		10			SM00550		S		YN231-YN501
0541WY	18		PA		9-8	33-25-31	D11610		1			SM00541		S		YC051-YL999, YR301-YR328
0541WY	18		PA		6-11	33-25-31	D11610		1			SM00541		S		YN231-YN501
0542WV	22		PA		9-8	33-27-31	D11610		2			SM00542		S		YC051-YL999, YR301-YR328
0542WV	22		PA		7-0	33-27-31	D11610		2			SM00542		S		YN231-YN501
0543WG	22		PA		9-8	33-27-31	D11610		3			SM00543		S		YC051-YL999, YR301-YR328
0543WG	22		PA		7-0	33-27-31	D11610		3			SM00543		S		YN231-YN501
0544WO	22		PA		9-8	33-27-31	D11610		4			SM00544		S		YC051-YL999, YR301-YR328
0544WO	22		PA		7-0	33-27-31	D11610		4			SM00544		S		YN231-YN501
0545V	22		PA		9-8	33-27-31	D11610		5			SM00545		S		YC051-YL999, YR301-YR328
0545V	22		PA		7-0	33-27-31	D11610		5			SM00545		S		YN231-YN501
0546N	18		PA		9-8	33-23-21	D11610		6			SM00546		S		YC051-YL999, YR301-YR328
0546N	18		PA		6-11	33-23-21	D11610		6			SM00546		S		YN231-YN501
0547W	20		PA		9-8	33-25-31	D11610		7			SM00547		S		YC051-YL999, YR301-YR328
0547W	20		PA		6-11	33-25-31	D11610		7			SM00547		S		YN231-YN501
0548O	18		PA		9-8	33-23-21	D11610		8			SM00548		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)										
0548O	18		PA		6-11	33-23-21	D11610		8		SM00548		S		YN231-YN501
0549A	16		CQ		9-8	35-21-31	D11610		11		SM00549		S		YC051-YL999, YR301-YR328
0549A	16		CQ		7-0	35-21-31	D11610		11		SM00549		S		YN231-YN501
0550K	18		PA		9-8	33-27-31	D11610		10		SM00550		S		YC051-YL999, YR301-YR328
0550K	18		PA		7-0	33-27-31	D11610		10		SM00550		S		YN231-YN501
0551WY	18		PA		8-7	33-25-31	D11612		1		SM00561		S		YC051-YL999, YR301-YR328
0551WY	18		PA		7-5	33-25-31	D11612		1		SM00561		S		YN231-YN501
0552WV	22		PA		8-7	33-27-31	D11612		2		SM00562		S		YC051-YL999, YR301-YR328
0552WV	22		PA		7-6	33-27-31	D11612		2		SM00562		S		YN231-YN501
0553WG	22		PA		8-7	33-27-31	D11612		3		SM00563		S		YC051-YL999, YR301-YR328
0553WG	22		PA		7-6	33-27-31	D11612		3		SM00563		S		YN231-YN501
0554WO	22		PA		8-7	33-27-31	D11612		4		SM00564		S		YC051-YL999, YR301-YR328
0554WO	22		PA		7-6	33-27-31	D11612		4		SM00564		S		YN231-YN501
0555V	22		PA		8-7	33-27-31	D11612		5		SM00565		S		YC051-YL999, YR301-YR328
0555V	22		PA		7-6	33-27-31	D11612		5		SM00565		S		YN231-YN501
0556N	18		PA		8-7	33-23-21	D11612		6		SM00566		S		YC051-YL999, YR301-YR328
0556N	18		PA		7-5	33-23-21	D11612		6		SM00566		S		YN231-YN501
0557W	20		PA		8-7	33-25-31	D11612		7		SM00567		S		YC051-YL999, YR301-YR328
0557W	20		PA		7-5	33-25-31	D11612		7		SM00567		S		YN231-YN501
0558O	18		PA		8-7	33-23-21	D11612		8		SM00568		S		YC051-YL999, YR301-YR328
0558O	18		PA		7-5	33-23-21	D11612		8		SM00568		S		YN231-YN501
0559A	16		CQ		8-7	35-21-31	D11612		11		SM00569		S		YC051-YL999, YR301-YR328
0559A	16		CQ		7-6	35-21-31	D11612		11		SM00569		S		YN231-YN501
0560K	18		PA		8-7	33-27-31	D11612		10		SM00570		S		YC051-YL999, YR301-YR328
0560K	18		PA		7-6	33-27-31	D11612		10		SM00570		S		YN231-YN501
0561WY	18		PA		8-0	33-25-31	D11614		1		SM00561		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 18

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)										
0561WY	18		PA		8-11	33-25-31	D11614		1		SM00561		S		YN231-YN501
0562WV	22		PA		8-0	33-27-31	D11614		2		SM00562		S		YC051-YL999, YR301-YR328
0562WV	22		PA		9-0	33-27-31	D11614		2		SM00562		S		YN231-YN501
0563WG	22		PA		8-0	33-27-31	D11614		3		SM00563		S		YC051-YL999, YR301-YR328
0563WG	22		PA		9-0	33-27-31	D11614		3		SM00563		S		YN231-YN501
0564WO	22		PA		8-0	33-27-31	D11614		4		SM00564		S		YC051-YL999, YR301-YR328
0564WO	22		PA		9-0	33-27-31	D11614		4		SM00564		S		YN231-YN501
0565V	22		PA		8-0	33-27-31	D11614		5		SM00565		S		YC051-YL999, YR301-YR328
0565V	22		PA		9-0	33-27-31	D11614		5		SM00565		S		YN231-YN501
0566N	18		PA		8-0	33-23-21	D11614		6		SM00566		S		YC051-YL999, YR301-YR328
0566N	18		PA		8-11	33-23-21	D11614		6		SM00566		S		YN231-YN501
0567W	20		PA		8-0	33-25-31	D11614		7		SM00567		S		YC051-YL999, YR301-YR328
0567W	20		PA		8-11	33-25-31	D11614		7		SM00567		S		YN231-YN501
0568O	18		PA		8-0	33-23-21	D11614		8		SM00568		S		YC051-YL999, YR301-YR328
0568O	18		PA		8-11	33-23-21	D11614		8		SM00568		S		YN231-YN501
0569A	16		CQ		8-0	35-21-31	D11614		11		SM00569		S		YC051-YL999, YR301-YR328
0569A	16		CQ		9-0	35-21-31	D11614		11		SM00569		S		YN231-YN501
0570K	18		PA		8-0	33-27-31	D11614		10		SM00570		S		YC051-YL999, YR301-YR328
0570K	18		PA		9-0	33-27-31	D11614		10		SM00570		S		YN231-YN501
0571WY	18		PA		8-10	33-25-31	D11616		1		SM00581		S		YC051-YL999, YR301-YR328
0571WY	18		PA		8-7	33-25-31	D11616		1		SM00581		S		YN231-YN501
0572WV	22		PA		8-10	33-27-31	D11616		2		SM00582		S		YC051-YL999, YR301-YR328
0572WV	22		PA		8-7	33-27-31	D11616		2		SM00582		S		YN231-YN501
0573WG	22		PA		8-10	33-27-31	D11616		3		SM00583		S		YC051-YL999, YR301-YR328
0573WG	22		PA		8-7	33-27-31	D11616		3		SM00583		S		YN231-YN501
0574WO	22		PA		8-10	33-27-31	D11616		4		SM00584		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 19

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
0574WO	22		PA		8-7	33-27-31		D11616				4	SM00584		S	YN231-YN501
0575V	22		PA		8-10	33-27-31		D11616				5	SM00585		S	YC051-YL999, YR301-YR328
0575V	22		PA		8-7	33-27-31		D11616				5	SM00585		S	YN231-YN501
0576N	18		PA		8-10	33-23-21		D11616				6	SM00586		S	YC051-YL999, YR301-YR328
0576N	18		PA		8-7	33-23-21		D11616				6	SM00586		S	YN231-YN501
0577W	20		PA		8-10	33-25-31		D11616				7	SM00587		S	YC051-YL999, YR301-YR328
0577W	20		PA		8-7	33-25-31		D11616				7	SM00587		S	YN231-YN501
0578O	18		PA		8-10	33-23-21		D11616				8	SM00588		S	YC051-YL999, YR301-YR328
0578O	18		PA		8-7	33-23-21		D11616				8	SM00588		S	YN231-YN501
0579A	16		CQ		8-10	35-21-31		D11616				11	SM00589		S	YC051-YL999, YR301-YR328
0579A	16		CQ		8-7	35-21-31		D11616				11	SM00589		S	YN231-YN501
0580K	18		PA		8-10	33-27-31		D11616				10	SM00590		S	YC051-YL999, YR301-YR328
0580K	18		PA		8-7	33-27-31		D11616				10	SM00590		S	YN231-YN501
0581WY	18		PA		8-1	33-25-31		D11618				1	SM00581		S	YC051-YL999, YR301-YR328
0581WY	18		PA		9-2	33-25-31		D11618				1	SM00581		S	YN231-YN501
0582WV	22		PA		8-1	33-27-31		D11618				2	SM00582		S	YC051-YL999, YR301-YR328
0582WV	22		PA		9-2	33-27-31		D11618				2	SM00582		S	YN231-YN501
0583WG	22		PA		8-1	33-27-31		D11618				3	SM00583		S	YC051-YL999, YR301-YR328
0583WG	22		PA		9-2	33-27-31		D11618				3	SM00583		S	YN231-YN501
0584WO	22		PA		8-1	33-27-31		D11618				4	SM00584		S	YC051-YL999, YR301-YR328
0584WO	22		PA		9-2	33-27-31		D11618				4	SM00584		S	YN231-YN501
0585V	22		PA		8-1	33-27-31		D11618				5	SM00585		S	YC051-YL999, YR301-YR328
0585V	22		PA		9-2	33-27-31		D11618				5	SM00585		S	YN231-YN501
0586N	18		PA		8-1	33-23-21		D11618				6	SM00586		S	YC051-YL999, YR301-YR328
0586N	18		PA		9-2	33-23-21		D11618				6	SM00586		S	YN231-YN501
0587W	20		PA		8-1	33-25-31		D11618				7	SM00587		S	YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 20

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
0587W	20		PA		9-2	33-25-31		D11618	7			SM00587		S		YN231-YN501
0588O	18		PA		8-1	33-23-21		D11618	8			SM00588		S		YC051-YL999, YR301-YR328
0588O	18		PA		9-2	33-23-21		D11618	8			SM00588		S		YN231-YN501
0589A	16		CQ		8-1	35-21-31		D11618	11			SM00589		S		YC051-YL999, YR301-YR328
0589A	16		CQ		9-2	35-21-31		D11618	11			SM00589		S		YN231-YN501
0590K	18		PA		8-1	33-27-31		D11618	10			SM00590		S		YC051-YL999, YR301-YR328
0590K	18		PA		9-2	33-27-31		D11618	10			SM00590		S		YN231-YN501
0591WY	18		PA		8-10	33-25-31		D11620	1			SM00601		S		YC051-YL999, YR301-YR328
0591WY	18		PA		11-7	33-25-31		D11620	1			SM00641		S		YN231-YN501
0592WV	22		PA		8-10	33-27-31		D11620	2			SM00602		S		YC051-YL999, YR301-YR328
0592WV	22		PA		11-7	33-27-31		D11620	2			SM00642		S		YN231-YN501
0593WG	22		PA		8-10	33-27-31		D11620	3			SM00603		S		YC051-YL999, YR301-YR328
0593WG	22		PA		11-7	33-27-31		D11620	3			SM00643		S		YN231-YN501
0594WO	22		PA		8-10	33-27-31		D11620	4			SM00604		S		YC051-YL999, YR301-YR328
0594WO	22		PA		11-7	33-27-31		D11620	4			SM00644		S		YN231-YN501
0595V	22		PA		8-10	33-27-31		D11620	5			SM00605		S		YC051-YL999, YR301-YR328
0595V	22		PA		11-7	33-27-31		D11620	5			SM00645		S		YN231-YN501
0596N	18		PA		8-10	33-23-21		D11620	6			SM00606		S		YC051-YL999, YR301-YR328
0596N	18		PA		11-7	33-23-21		D11620	6			SM00646		S		YN231-YN501
0597W	20		PA		8-10	33-25-31		D11620	7			SM00607		S		YC051-YL999, YR301-YR328
0597W	20		PA		11-7	33-25-31		D11620	7			SM00647		S		YN231-YN501
0598O	18		PA		8-10	33-23-21		D11620	8			SM00608		S		YC051-YL999, YR301-YR328
0598O	18		PA		11-7	33-23-21		D11620	8			SM00648		S		YN231-YN501
0599A	16		CQ		8-10	35-21-31		D11620	11			SM00609		S		YC051-YL999, YR301-YR328
0599A	16		CQ		11-7	35-21-31		D11620	11			SM00649		S		YN231-YN501
0600K	18		PA		8-10	33-27-31		D11620	10			SM00610		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 21

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To						
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)												
0600K	18		PA		11-7	33-27-31		D11620			10			SM00650		S	YN231-YN501
0601WY	18		PA		8-1	33-25-31		D11622			1			SM00601		S	YC051-YL999, YR301-YR328
0602WV	22		PA		8-1	33-27-31		D11622			2			SM00602		S	YC051-YL999, YR301-YR328
0603WG	22		PA		8-1	33-27-31		D11622			3			SM00603		S	YC051-YL999, YR301-YR328
0604WO	22		PA		8-1	33-27-31		D11622			4			SM00604		S	YC051-YL999, YR301-YR328
0605V	22		PA		8-1	33-27-31		D11622			5			SM00605		S	YC051-YL999, YR301-YR328
0606N	18		PA		8-1	33-23-21		D11622			6			SM00606		S	YC051-YL999, YR301-YR328
0607W	20		PA		8-1	33-25-31		D11622			7			SM00607		S	YC051-YL999, YR301-YR328
0608O	18		PA		8-1	33-23-21		D11622			8			SM00608		S	YC051-YL999, YR301-YR328
0609A	16		CQ		8-1	35-21-31		D11622			11			SM00609		S	YC051-YL999, YR301-YR328
0610K	18		PA		8-1	33-27-31		D11622			10			SM00610		S	YC051-YL999, YR301-YR328
0611WY	18		PA		8-7	33-25-31		D11624			1			SM00621		S	YC051-YL999, YR301-YR328
0612WV	22		PA		8-7	33-27-31		D11624			2			SM00622		S	YC051-YL999, YR301-YR328
0613WG	22		PA		8-7	33-27-31		D11624			3			SM00623		S	YC051-YL999, YR301-YR328
0614WO	22		PA		8-7	33-27-31		D11624			4			SM00624		S	YC051-YL999, YR301-YR328
0615V	22		PA		8-7	33-27-31		D11624			5			SM00625		S	YC051-YL999, YR301-YR328
0616N	18		PA		8-7	33-23-21		D11624			6			SM00626		S	YC051-YL999, YR301-YR328
0617W	20		PA		8-7	33-25-31		D11624			7			SM00627		S	YC051-YL999, YR301-YR328
0618O	18		PA		8-7	33-23-21		D11624			8			SM00628		S	YC051-YL999, YR301-YR328
0619A	16		CQ		8-7	35-21-31		D11624			11			SM00629		S	YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 22

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)												
0620K	18		PA		8-7		33-27-31	D11624		10		SM00630		S		YC051-YL999, YR301-YR328	
0621WY	18		PA		7-3		33-25-31	D11626		1		SM00621		S		YC051-YL999, YR301-YR328	
0622WV	22		PA		7-3		33-27-31	D11626		2		SM00622		S		YC051-YL999, YR301-YR328	
0623WG	22		PA		7-3		33-27-31	D11626		3		SM00623		S		YC051-YL999, YR301-YR328	
0624WO	22		PA		7-3		33-27-31	D11626		4		SM00624		S		YC051-YL999, YR301-YR328	
0625V	22		PA		7-3		33-27-31	D11626		5		SM00625		S		YC051-YL999, YR301-YR328	
0626N	18		PA		7-3		33-23-21	D11626		6		SM00626		S		YC051-YL999, YR301-YR328	
0627W	20		PA		7-3		33-25-31	D11626		7		SM00627		S		YC051-YL999, YR301-YR328	
0628O	18		PA		7-3		33-23-21	D11626		8		SM00628		S		YC051-YL999, YR301-YR328	
0629A	16		CQ		7-3		35-21-31	D11626		11		SM00629		S		YC051-YL999, YR301-YR328	
0630K	18		PA		7-3		33-27-31	D11626		10		SM00630		S		YC051-YL999, YR301-YR328	
0631WY	18		PA		7-11		33-25-31	D11628		1		SM00641		S		YC051-YL999, YR301-YR328	
0632WV	22		PA		7-11		33-27-31	D11628		2		SM00642		S		YC051-YL999, YR301-YR328	
0633WG	22		PA		7-11		33-27-31	D11628		3		SM00643		S		YC051-YL999, YR301-YR328	
0634WO	22		PA		7-11		33-27-31	D11628		4		SM00644		S		YC051-YL999, YR301-YR328	
0635V	22		PA		7-11		33-27-31	D11628		5		SM00645		S		YC051-YL999, YR301-YR328	
0636N	18		PA		7-11		33-23-21	D11628		6		SM00646		S		YC051-YL999, YR301-YR328	
0637W	20		PA		7-11		33-25-31	D11628		7		SM00647		S		YC051-YL999, YR301-YR328	
0638O	18		PA		7-11		33-23-21	D11628		8		SM00648		S		YC051-YL999, YR301-YR328	

WIRE LIST

D280A108

91-21-11

Section W4250

Page 23

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
0639A	16		CQ		7-11	35-21-31		D11628		11		SM00649		S		YC051-YL999, YR301-YR328
0640K	18		PA		7-11	33-27-31		D11628		10		SM00650		S		YC051-YL999, YR301-YR328
0641WY	18		PA		10-10	33-25-31		D11630		1		SM00641		S		YC051-YL999, YR301-YR328
0641WY	18		PA		8-5	33-25-31		D11630		1		SM00641		S		YN231-YN501
0642WV	22		PA		10-10	33-27-31		D11630		2		SM00642		S		YC051-YL999, YR301-YR328
0642WV	22		PA		8-6	33-27-31		D11630		2		SM00642		S		YN231-YN501
0643WG	22		PA		10-10	33-27-31		D11630		3		SM00643		S		YC051-YL999, YR301-YR328
0643WG	22		PA		8-6	33-27-31		D11630		3		SM00643		S		YN231-YN501
0644WO	22		PA		10-10	33-27-31		D11630		4		SM00644		S		YC051-YL999, YR301-YR328
0644WO	22		PA		8-6	33-27-31		D11630		4		SM00644		S		YN231-YN501
0645V	22		PA		10-10	33-27-31		D11630		5		SM00645		S		YC051-YL999, YR301-YR328
0645V	22		PA		8-6	33-27-31		D11630		5		SM00645		S		YN231-YN501
0646N	18		PA		10-10	33-23-21		D11630		6		SM00646		S		YC051-YL999, YR301-YR328
0646N	18		PA		8-5	33-23-21		D11630		6		SM00646		S		YN231-YN501
0647W	20		PA		10-10	33-25-31		D11630		7		SM00647		S		YC051-YL999, YR301-YR328
0647W	20		PA		8-5	33-25-31		D11630		7		SM00647		S		YN231-YN501
0648O	18		PA		10-10	33-23-21		D11630		8		SM00648		S		YC051-YL999, YR301-YR328
0648O	18		PA		8-5	33-23-21		D11630		8		SM00648		S		YN231-YN501
0649A	16		CQ		10-10	35-21-31		D11630		11		SM00649		S		YC051-YL999, YR301-YR328
0649A	16		CQ		8-6	35-21-31		D11630		11		SM00649		S		YN231-YN501
0650K	18		PA		10-10	33-27-31		D11630		10		SM00650		S		YC051-YL999, YR301-YR328
0650K	18		PA		8-6	33-27-31		D11630		10		SM00650		S		YN231-YN501
0651WY	18		PA		6-8	33-25-31		D11632		1		SM00661		S		YC051-YL999, YR301-YR328
0651WY	18		PA		8-11	33-25-31		D11632		1		SM00641		S		YN231-YN501
0652WV	22		PA		6-8	33-27-31		D11632		2		SM00662		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 24

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
0652WV	22		PA		9-0	33-27-31	D11632		2			SM00642		S		YN231-YN501
0653WG	22		PA		6-8	33-27-31	D11632		3			SM00663		S		YC051-YL999, YR301-YR328
0653WG	22		PA		9-0	33-27-31	D11632		3			SM00643		S		YN231-YN501
0654WO	22		PA		6-8	33-27-31	D11632		4			SM00664		S		YC051-YL999, YR301-YR328
0654WO	22		PA		9-0	33-27-31	D11632		4			SM00644		S		YN231-YN501
0655V	22		PA		6-8	33-27-31	D11632		5			SM00665		S		YC051-YL999, YR301-YR328
0655V	22		PA		9-0	33-27-31	D11632		5			SM00645		S		YN231-YN501
0656N	18		PA		6-8	33-23-21	D11632		6			SM00666		S		YC051-YL999, YR301-YR328
0656N	18		PA		8-11	33-23-21	D11632		6			SM00646		S		YN231-YN501
0657W	20		PA		6-8	33-25-31	D11632		7			SM00667		S		YC051-YL999, YR301-YR328
0657W	20		PA		8-11	33-25-31	D11632		7			SM00647		S		YN231-YN501
0658O	18		PA		6-8	33-23-21	D11632		8			SM00668		S		YC051-YL999, YR301-YR328
0658O	18		PA		8-11	33-23-21	D11632		8			SM00648		S		YN231-YN501
0659A	16		CQ		6-8	35-21-31	D11632		11			SM00669		S		YC051-YL999, YR301-YR328
0659A	16		CQ		9-0	35-21-31	D11632		11			SM00649		S		YN231-YN501
0660K	18		PA		6-8	33-27-31	D11632		10			SM00670		S		YC051-YL999, YR301-YR328
0660K	18		PA		9-0	33-27-31	D11632		10			SM00650		S		YN231-YN501
0661WY	18		PA		7-3	33-25-31	D11634		1			SM00661		S		YC051-YL999, YR301-YR328
0661WY	18		PA		8-2	33-25-31	D11634		1			SM00661		S		YN231-YN501
0662WV	22		PA		7-3	33-27-31	D11634		2			SM00662		S		YC051-YL999, YR301-YR328
0662WV	22		PA		8-2	33-27-31	D11634		2			SM00662		S		YN231-YN501
0663WG	22		PA		7-3	33-27-31	D11634		3			SM00663		S		YC051-YL999, YR301-YR328
0663WG	22		PA		8-2	33-27-31	D11634		3			SM00663		S		YN231-YN501
0664WO	22		PA		7-3	33-27-31	D11634		4			SM00664		S		YC051-YL999, YR301-YR328
0664WO	22		PA		8-2	33-27-31	D11634		4			SM00664		S		YN231-YN501
0665V	22		PA		7-3	33-27-31	D11634		5			SM00665		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 25

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)										
0665V	22		PA		8-2	33-27-31	D11634		5		SM00665		S		YN231-YN501
0666N	18		PA		7-3	33-23-21	D11634		6		SM00666		S		YC051-YL999, YR301-YR328
0666N	18		PA		8-2	33-23-21	D11634		6		SM00666		S		YN231-YN501
0667W	20		PA		7-3	33-25-31	D11634		7		SM00667		S		YC051-YL999, YR301-YR328
0667W	20		PA		8-2	33-25-31	D11634		7		SM00667		S		YN231-YN501
0668O	18		PA		7-3	33-23-21	D11634		8		SM00668		S		YC051-YL999, YR301-YR328
0668O	18		PA		8-2	33-23-21	D11634		8		SM00668		S		YN231-YN501
0669A	16		CQ		7-3	35-21-31	D11634		11		SM00669		S		YC051-YL999, YR301-YR328
0669A	16		CQ		8-2	35-21-31	D11634		11		SM00669		S		YN231-YN501
0670K	18		PA		7-3	33-27-31	D11634		10		SM00670		S		YC051-YL999, YR301-YR328
0670K	18		PA		8-2	33-27-31	D11634		10		SM00670		S		YN231-YN501
0671WY	18		PA		7-11	33-25-31	D11636		1		SM00681		S		YC051-YL999, YR301-YR328
0671WY	18		PA		7-9	33-25-31	D11636		1		SM00661		S		YN231-YN501
0672WV	22		PA		7-11	33-27-31	D11636		2		SM00682		S		YC051-YL999, YR301-YR328
0672WV	22		PA		7-6	33-27-31	D11636		2		SM00662		S		YN231-YN501
0673WG	22		PA		7-11	33-27-31	D11636		3		SM00683		S		YC051-YL999, YR301-YR328
0673WG	22		PA		7-6	33-27-31	D11636		3		SM00663		S		YN231-YN501
0674WO	22		PA		7-11	33-27-31	D11636		4		SM00684		S		YC051-YL999, YR301-YR328
0674WO	22		PA		7-6	33-27-31	D11636		4		SM00664		S		YN231-YN501
0675V	22		PA		7-11	33-27-31	D11636		5		SM00685		S		YC051-YL999, YR301-YR328
0675V	22		PA		7-6	33-27-31	D11636		5		SM00665		S		YN231-YN501
0676N	18		PA		7-11	33-23-21	D11636		6		SM00686		S		YC051-YL999, YR301-YR328
0676N	18		PA		7-9	33-23-21	D11636		6		SM00666		S		YN231-YN501
0677W	20		PA		7-11	33-25-31	D11636		7		SM00687		S		YC051-YL999, YR301-YR328
0677W	20		PA		7-9	33-25-31	D11636		7		SM00667		S		YN231-YN501
0678O	18		PA		7-11	33-23-21	D11636		8		SM00688		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 26

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
0678O	18		PA		7-9	33-23-21		D11636	8			SM00668		S		YN231-YN501
0679A	16		CQ		7-11	35-21-31		D11636	11			SM00689		S		YC051-YL999, YR301-YR328
0679A	16		CQ		7-6	35-21-31		D11636	11			SM00669		S		YN231-YN501
0680K	18		PA		7-11	33-27-31		D11636	10			SM00690		S		YC051-YL999, YR301-YR328
0680K	18		PA		7-6	33-27-31		D11636	10			SM00670		S		YN231-YN501
0681WY	18		PA		7-4	33-25-31		D11638	1			SM00681		S		YC051-YL999, YR301-YR328
0681WY	18		PA		8-8	33-25-31		D11638	1			SM00681		S		YN231-YN501
0682WV	22		PA		7-4	33-27-31		D11638	2			SM00682		S		YC051-YL999, YR301-YR328
0682WV	22		PA		8-8	33-27-32		D11638	2			SM00682		S		YN231-YN501
0683WG	22		PA		7-4	33-27-31		D11638	3			SM00683		S		YC051-YL999, YR301-YR328
0683WG	22		PA		8-8	33-27-32		D11638	3			SM00683		S		YN231-YN501
0684WO	22		PA		7-4	33-27-31		D11638	4			SM00684		S		YC051-YL999, YR301-YR328
0684WO	22		PA		8-8	33-27-32		D11638	4			SM00684		S		YN231-YN501
0685V	22		PA		7-4	33-27-31		D11638	5			SM00685		S		YC051-YL999, YR301-YR328
0685V	22		PA		8-8	33-27-32		D11638	5			SM00685		S		YN231-YN501
0686N	18		PA		7-4	33-23-21		D11638	6			SM00686		S		YC051-YL999, YR301-YR328
0686N	18		PA		8-8	33-23-21		D11638	6			SM00686		S		YN231-YN501
0687W	20		PA		7-4	33-25-31		D11638	7			SM00687		S		YC051-YL999, YR301-YR328
0687W	20		PA		8-8	33-25-31		D11638	7			SM00687		S		YN231-YN501
0688O	18		PA		7-4	33-23-21		D11638	8			SM00688		S		YC051-YL999, YR301-YR328
0688O	18		PA		8-8	33-23-21		D11638	8			SM00688		S		YN231-YN501
0689A	16		CQ		7-4	35-21-31		D11638	11			SM00689		S		YC051-YL999, YR301-YR328
0689A	16		CQ		8-8	35-21-31		D11638	11			SM00689		S		YN231-YN501
0690K	18		PA		7-4	33-27-31		D11638	10			SM00690		S		YC051-YL999, YR301-YR328
0690K	18		PA		8-8	33-27-32		D11638	10			SM00690		S		YN231-YN501
0691WY	18		PA		9-0	33-25-31		D11640	1			SM00701		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 27

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)										
0691WY	18		PA		7-7	33-25-31	D11640				SM00681		S		YN231-YN501
0692WV	22		PA		9-0	33-27-31	D11640				SM00702		S		YC051-YL999, YR301-YR328
0692WV	22		PA		7-7	33-27-32	D11640				SM00682		S		YN231-YN501
0693WG	22		PA		9-0	33-27-31	D11640				SM00703		S		YC051-YL999, YR301-YR328
0693WG	22		PA		7-7	33-27-32	D11640				SM00683		S		YN231-YN501
0694WO	22		PA		9-0	33-27-31	D11640				SM00704		S		YC051-YL999, YR301-YR328
0694WO	22		PA		7-7	33-27-32	D11640				SM00684		S		YN231-YN501
0695V	22		PA		9-0	33-27-31	D11640				SM00705		S		YC051-YL999, YR301-YR328
0695V	22		PA		7-7	33-27-32	D11640				SM00685		S		YN231-YN501
0696N	18		PA		9-0	33-23-21	D11640				SM00706		S		YC051-YL999, YR301-YR328
0696N	18		PA		7-7	33-23-21	D11640				SM00686		S		YN231-YN501
0697W	20		PA		9-0	33-25-31	D11640				SM00707		S		YC051-YL999, YR301-YR328
0697W	20		PA		7-7	33-25-31	D11640				SM00687		S		YN231-YN501
0698O	18		PA		9-0	33-23-21	D11640				SM00708		S		YC051-YL999, YR301-YR328
0698O	18		PA		7-7	33-23-21	D11640				SM00688		S		YN231-YN501
0699A	16		CQ		9-0	35-21-31	D11640				SM00709		S		YC051-YL999, YR301-YR328
0699A	16		CQ		7-7	35-21-31	D11640				SM00689		S		YN231-YN501
0700K	18		PA		9-0	33-27-31	D11640				SM00710		S		YC051-YL999, YR301-YR328
0700K	18		PA		7-7	33-27-32	D11640				SM00690		S		YN231-YN501
0701WY	18		PA		7-7	33-25-31	D11642				SM00701		S		YC051-YL999, YR301-YR328
0701WY	18		PA		7-2	33-25-32	D11642				SM00701		S		YN231-YN501
0702WV	22		PA		7-7	33-27-31	D11642				SM00702		S		YC051-YL999, YR301-YR328
0702WV	22		PA		7-2	33-27-32	D11642				SM00702		S		YN231-YN501
0703WG	22		PA		7-7	33-27-31	D11642				SM00703		S		YC051-YL999, YR301-YR328
0703WG	22		PA		7-2	33-27-32	D11642				SM00703		S		YN231-YN501
0704WO	22		PA		7-7	33-27-31	D11642				SM00704		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 28

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250			P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
0704WO	22		PA		7-2	33-27-32	D11642				SM00704		S		YN231-YN501
0705V	22		PA		7-7	33-27-31	D11642				SM00705		S		YC051-YL999, YR301-YR328
0705V	22		PA		7-2	33-27-32	D11642				SM00705		S		YN231-YN501
0706N	18		PA		7-7	33-23-21	D11642				SM00706		S		YC051-YL999, YR301-YR328
0706N	18		PA		7-2	33-23-22	D11642				SM00706		S		YN231-YN501
0707W	20		PA		7-7	33-25-31	D11642				SM00707		S		YC051-YL999, YR301-YR328
0707W	20		PA		7-2	33-25-32	D11642				SM00707		S		YN231-YN501
0708O	18		PA		7-7	33-23-21	D11642				SM00708		S		YC051-YL999, YR301-YR328
0708O	18		PA		7-2	33-23-22	D11642				SM00708		S		YN231-YN501
0709A	16		CQ		7-7	35-21-31	D11642				SM00709		S		YC051-YL999, YR301-YR328
0709A	16		CQ		7-2	35-21-31	D11642				SM00709		S		YN231-YN501
0710K	18		PA		7-7	33-27-31	D11642				SM00710		S		YC051-YL999, YR301-YR328
0710K	18		PA		7-2	33-27-32	D11642				SM00710		S		YN231-YN501
0711WY	18		PA		8-4	33-25-31	D11644				SM00721		S		YC051-YL999, YR301-YR328
0711WY	18		PA		10-8	33-25-32	D11644				SM00701		S		YN231-YN501
0712WV	22		PA		8-4	33-27-31	D11644				SM00722		S		YC051-YL999, YR301-YR328
0712WV	22		PA		10-7	33-27-32	D11644				SM00702		S		YN231-YN501
0713WG	22		PA		8-4	33-27-31	D11644				SM00723		S		YC051-YL999, YR301-YR328
0713WG	22		PA		10-7	33-27-32	D11644				SM00703		S		YN231-YN501
0714WO	22		PA		8-4	33-27-31	D11644				SM00724		S		YC051-YL999, YR301-YR328
0714WO	22		PA		10-7	33-27-32	D11644				SM00704		S		YN231-YN501
0715V	22		PA		8-4	33-27-31	D11644				SM00725		S		YC051-YL999, YR301-YR328
0715V	22		PA		10-7	33-27-32	D11644				SM00705		S		YN231-YN501
0716N	18		PA		8-4	33-23-21	D11644				SM00726		S		YC051-YL999, YR301-YR328
0716N	18		PA		10-8	33-23-22	D11644				SM00706		S		YN231-YN501
0717W	20		PA		8-4	33-25-31	D11644				SM00727		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 29

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)										
0717W	20		PA		10-8	33-25-32	D11644		7		SM00707		S		YN231-YN501
0718O	18		PA		8-4	33-23-21	D11644		8		SM00728		S		YC051-YL999, YR301-YR328
0718O	18		PA		10-8	33-23-22	D11644		8		SM00708		S		YN231-YN501
0719A	16		CQ		8-4	35-21-31	D11644		11		SM00729		S		YC051-YL999, YR301-YR328
0719A	16		CQ		10-7	35-21-31	D11644		11		SM00709		S		YN231-YN501
0720K	18		PA		8-4	33-27-31	D11644		10		SM00730		S		YC051-YL999, YR301-YR328
0720K	18		PA		10-7	33-27-32	D11644		10		SM00710		S		YN231-YN501
0721WY	18		PA		10-4	33-25-31	D11646		1		SM00721		S		YC051-YL999, YR301-YR328
0721WY	18		PA		11-2	33-25-32	D11646		1		SM00721		S		YN231-YN501
0722WV	22		PA		10-4	33-27-31	D11646		2		SM00722		S		YC051-YL999, YR301-YR328
0722WV	22		PA		11-2	33-27-32	D11646		2		SM00722		S		YN231-YN501
0723WG	22		PA		10-4	33-27-31	D11646		3		SM00723		S		YC051-YL999, YR301-YR328
0723WG	22		PA		11-2	33-27-32	D11646		3		SM00723		S		YN231-YN501
0724WO	22		PA		10-4	33-27-31	D11646		4		SM00724		S		YC051-YL999, YR301-YR328
0724WO	22		PA		11-2	33-27-32	D11646		4		SM00724		S		YN231-YN501
0725V	22		PA		10-4	33-27-31	D11646		5		SM00725		S		YC051-YL999, YR301-YR328
0725V	22		PA		11-2	33-27-32	D11646		5		SM00725		S		YN231-YN501
0726N	18		PA		10-4	33-23-21	D11646		6		SM00726		S		YC051-YL999, YR301-YR328
0726N	18		PA		11-2	33-23-22	D11646		6		SM00726		S		YN231-YN501
0727W	20		PA		10-4	33-25-31	D11646		7		SM00727		S		YC051-YL999, YR301-YR328
0727W	20		PA		11-2	33-25-32	D11646		7		SM00727		S		YN231-YN501
0728O	18		PA		10-4	33-23-21	D11646		8		SM00728		S		YC051-YL999, YR301-YR328
0728O	18		PA		11-2	33-23-22	D11646		8		SM00728		S		YN231-YN501
0729A	16		CQ		10-4	35-21-31	D11646		11		SM00729		S		YC051-YL999, YR301-YR328
0729A	16		CQ		11-2	35-21-31	D11646		11		SM00729		S		YN231-YN501
0730K	18		PA		10-4	33-27-31	D11646		10		SM00730		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 30

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
0730K	18		PA		11-2	33-27-32		D11646	10			SM00730		S		YN231-YN501
0731WY	18		PA		9-0	33-25-32		D11648	1			SM00741		S		YC051-YL999, YR301-YR328
0731WY	18		PA		10-3	33-25-32		D11648	1			SM00721		S		YN231-YN501
0732WV	22		PA		9-0	33-27-32		D11648	2			SM00742		S		YC051-YL999, YR301-YR328
0732WV	22		PA		10-4	33-27-32		D11648	2			SM00722		S		YN231-YN501
0733WG	22		PA		9-0	33-27-32		D11648	3			SM00743		S		YC051-YL999, YR301-YR328
0733WG	22		PA		10-4	33-27-32		D11648	3			SM00723		S		YN231-YN501
0734WO	22		PA		9-0	33-27-32		D11648	4			SM00744		S		YC051-YL999, YR301-YR328
0734WO	22		PA		10-4	33-27-32		D11648	4			SM00724		S		YN231-YN501
0735V	22		PA		9-0	33-27-32		D11648	5			SM00745		S		YC051-YL999, YR301-YR328
0735V	22		PA		10-4	33-27-32		D11648	5			SM00725		S		YN231-YN501
0736N	18		PA		9-0	33-23-22		D11648	6			SM00746		S		YC051-YL999, YR301-YR328
0736N	18		PA		10-3	33-23-22		D11648	6			SM00726		S		YN231-YN501
0737W	20		PA		9-0	33-25-32		D11648	7			SM00747		S		YC051-YL999, YR301-YR328
0737W	20		PA		10-3	33-25-32		D11648	7			SM00727		S		YN231-YN501
0738O	18		PA		9-0	33-23-22		D11648	8			SM00748		S		YC051-YL999, YR301-YR328
0738O	18		PA		10-3	33-23-22		D11648	8			SM00728		S		YN231-YN501
0739A	16		CQ		9-0	35-21-31		D11648	11			SM00749		S		YC051-YL999, YR301-YR328
0739A	16		CQ		10-4	35-21-31		D11648	11			SM00729		S		YN231-YN501
0740K	18		PA		9-0	33-27-32		D11648	10			SM00750		S		YC051-YL999, YR301-YR328
0740K	18		PA		10-4	33-27-32		D11648	10			SM00730		S		YN231-YN501
0741WY	18		PA		8-3	33-25-32		D11650	1			SM00741		S		YC051-YL999, YR301-YR328
0741WY	18		PA		8-11	33-25-32		D11650	1			SM00741		S		YN231-YN501
0742WV	22		PA		8-3	33-27-32		D11650	2			SM00742		S		YC051-YL999, YR301-YR328
0742WV	22		PA		8-8	33-27-32		D11650	2			SM00742		S		YN231-YN501
0743WG	22		PA		8-3	33-27-32		D11650	3			SM00743		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 31

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)										
0743WG	22		PA		8-8	33-27-32	D11650				SM00743		S		YN231-YN501
0744WO	22		PA		8-3	33-27-32	D11650				SM00744		S		YC051-YL999, YR301-YR328
0744WO	22		PA		8-8	33-27-32	D11650				SM00744		S		YN231-YN501
0745V	22		PA		8-3	33-27-32	D11650				SM00745		S		YC051-YL999, YR301-YR328
0745V	22		PA		8-8	33-27-32	D11650				SM00745		S		YN231-YN501
0746N	18		PA		8-3	33-23-22	D11650				SM00746		S		YC051-YL999, YR301-YR328
0746N	18		PA		8-11	33-23-22	D11650				SM00746		S		YN231-YN501
0747W	20		PA		8-3	33-25-32	D11650				SM00747		S		YC051-YL999, YR301-YR328
0747W	20		PA		8-11	33-25-32	D11650				SM00747		S		YN231-YN501
0748O	18		PA		8-3	33-23-22	D11650				SM00748		S		YC051-YL999, YR301-YR328
0748O	18		PA		8-11	33-23-22	D11650				SM00748		S		YN231-YN501
0749A	16		CQ		8-3	35-21-31	D11650				SM00749		S		YC051-YL999, YR301-YR328
0749A	16		CQ		8-8	35-21-31	D11650				SM00749		S		YN231-YN501
0750K	18		PA		8-3	33-27-32	D11650				SM00750		S		YC051-YL999, YR301-YR328
0750K	18		PA		8-8	33-27-32	D11650				SM00750		S		YN231-YN501
0751WY	18		PA		8-5	33-25-32	D11652				SM00761		S		YC051-YL999, YR301-YR328
0751WY	18		PA		10-9	33-25-32	D11652				SM00741		S		YN231-YN501
0752WV	22		PA		8-5	33-27-32	D11652				SM00762		S		YC051-YL999, YR301-YR328
0752WV	22		PA		10-8	33-27-32	D11652				SM00742		S		YN231-YN501
0753WG	22		PA		8-5	33-27-32	D11652				SM00763		S		YC051-YL999, YR301-YR328
0753WG	22		PA		10-8	33-27-32	D11652				SM00743		S		YN231-YN501
0754WO	22		PA		8-5	33-27-32	D11652				SM00764		S		YC051-YL999, YR301-YR328
0754WO	22		PA		10-8	33-27-32	D11652				SM00744		S		YN231-YN501
0755V	22		PA		8-5	33-27-32	D11652				SM00765		S		YC051-YL999, YR301-YR328
0755V	22		PA		10-8	33-27-32	D11652				SM00745		S		YN231-YN501
0756N	18		PA		8-5	33-23-22	D11652				SM00766		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 32

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
0756N	18		PA		10-9	33-23-22		D11652		6		SM00746		S		YN231-YN501
0757W	20		PA		8-5	33-25-32		D11652		7		SM00767		S		YC051-YL999, YR301-YR328
0757W	20		PA		10-9	33-25-32		D11652		7		SM00747		S		YN231-YN501
0758O	18		PA		8-5	33-23-22		D11652		8		SM00768		S		YC051-YL999, YR301-YR328
0758O	18		PA		10-9	33-23-22		D11652		8		SM00748		S		YN231-YN501
0759A	16		CQ		8-5	35-21-31		D11652		11		SM00769		S		YC051-YL999, YR301-YR328
0759A	16		CQ		10-8	35-21-31		D11652		11		SM00749		S		YN231-YN501
0760K	18		PA		8-5	33-27-32		D11652		10		SM00770		S		YC051-YL999, YR301-YR328
0760K	18		PA		10-8	33-27-32		D11652		10		SM00750		S		YN231-YN501
0761WY	18		PA		7-6	33-25-32		D11654		1		SM00761		S		YC051-YL999, YR301-YR328
0762WV	22		PA		7-6	33-27-32		D11654		2		SM00762		S		YC051-YL999, YR301-YR328
0763WG	22		PA		7-6	33-27-32		D11654		3		SM00763		S		YC051-YL999, YR301-YR328
0764WO	22		PA		7-6	33-27-32		D11654		4		SM00764		S		YC051-YL999, YR301-YR328
0765V	22		PA		7-6	33-27-32		D11654		5		SM00765		S		YC051-YL999, YR301-YR328
0766N	18		PA		7-6	33-23-22		D11654		6		SM00766		S		YC051-YL999, YR301-YR328
0767W	20		PA		7-6	33-25-32		D11654		7		SM00767		S		YC051-YL999, YR301-YR328
0768O	18		PA		7-6	33-23-22		D11654		8		SM00768		S		YC051-YL999, YR301-YR328
0769A	16		CQ		7-6	35-21-31		D11654		11		SM00769		S		YC051-YL999, YR301-YR328
0770K	18		PA		7-6	33-27-32		D11654		10		SM00770		S		YC051-YL999, YR301-YR328
0771WY	18		PA		8-7	33-25-32		D11656		1		SM00781		S		YC051-YL999, YR301-YR328
0772WV	22		PA		8-7	33-27-32		D11656		2		SM00782		S		YC051-YL999, YR301-YR328
0773WG	22		PA		8-7	33-27-32		D11656		3		SM00783		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 33

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
0774WO	22		PA		8-7		33-27-32	D11656		4		SM00784		S		YC051-YL999, YR301-YR328
0775V	22		PA		8-7		33-27-32	D11656		5		SM00785		S		YC051-YL999, YR301-YR328
0776N	18		PA		8-7		33-23-22	D11656		6		SM00786		S		YC051-YL999, YR301-YR328
0777W	20		PA		8-7		33-25-32	D11656		7		SM00787		S		YC051-YL999, YR301-YR328
0778O	18		PA		8-7		33-23-22	D11656		8		SM00788		S		YC051-YL999, YR301-YR328
0779A	16		CQ		8-7		35-21-31	D11656		11		SM00789		S		YC051-YL999, YR301-YR328
0780K	18		PA		8-7		33-27-32	D11656		10		SM00790		S		YC051-YL999, YR301-YR328
0781WY	18		PA		7-11		33-25-32	D11658		1		SM00781		S		YC051-YL999, YR301-YR328
0782WV	22		PA		7-11		33-27-32	D11658		2		SM00782		S		YC051-YL999, YR301-YR328
0783WG	22		PA		7-11		33-27-32	D11658		3		SM00783		S		YC051-YL999, YR301-YR328
0784WO	22		PA		7-11		33-27-32	D11658		4		SM00784		S		YC051-YL999, YR301-YR328
0785V	22		PA		7-11		33-27-32	D11658		5		SM00785		S		YC051-YL999, YR301-YR328
0786N	18		PA		7-11		33-23-22	D11658		6		SM00786		S		YC051-YL999, YR301-YR328
0787W	20		PA		7-11		33-25-32	D11658		7		SM00787		S		YC051-YL999, YR301-YR328
0788O	18		PA		7-11		33-23-22	D11658		8		SM00788		S		YC051-YL999, YR301-YR328
0789A	16		CQ		7-11		35-21-31	D11658		11		SM00789		S		YC051-YL999, YR301-YR328
0790K	18		PA		7-11		33-27-32	D11658		10		SM00790		S		YC051-YL999, YR301-YR328
0791WY	18		PA		9-1		33-25-32	D11660		1		SM00801		S		YC051-YL999, YR301-YR328
0792WV	22		PA		9-1		33-27-32	D11660		2		SM00802		S		YC051-YL999, YR301-YR328

WIRE LIST
D280A108

91-21-11
Section W4250
Page 34
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250			P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
0793WG	22		PA		9-1	33-27-32	D11660		3		SM00803		S		YC051-YL999, YR301-YR328
0794WO	22		PA		9-1	33-27-32	D11660		4		SM00804		S		YC051-YL999, YR301-YR328
0795V	22		PA		9-1	33-27-32	D11660		5		SM00805		S		YC051-YL999, YR301-YR328
0796N	18		PA		9-1	33-23-22	D11660		6		SM00806		S		YC051-YL999, YR301-YR328
0797W	20		PA		9-1	33-25-32	D11660		7		SM00807		S		YC051-YL999, YR301-YR328
0798O	18		PA		9-1	33-23-22	D11660		8		SM00808		S		YC051-YL999, YR301-YR328
0799A	16		CQ		9-1	35-21-31	D11660		11		SM00809		S		YC051-YL999, YR301-YR328
0800K	18		PA		9-1	33-27-32	D11660		10		SM00810		S		YC051-YL999, YR301-YR328
0801WY	18		PA		8-0	33-25-32	D11662		1		SM00801		S		YC051-YL999, YR301-YR328
0802WV	22		PA		8-0	33-27-32	D11662		2		SM00802		S		YC051-YL999, YR301-YR328
0803WG	22		PA		8-0	33-27-32	D11662		3		SM00803		S		YC051-YL999, YR301-YR328
0804WO	22		PA		8-0	33-27-32	D11662		4		SM00804		S		YC051-YL999, YR301-YR328
0805V	22		PA		8-0	33-27-32	D11662		5		SM00805		S		YC051-YL999, YR301-YR328
0806N	18		PA		8-0	33-23-22	D11662		6		SM00806		S		YC051-YL999, YR301-YR328
0807W	20		PA		8-0	33-25-32	D11662		7		SM00807		S		YC051-YL999, YR301-YR328
0808O	18		PA		8-0	33-23-22	D11662		8		SM00808		S		YC051-YL999, YR301-YR328
0809A	16		CQ		8-0	35-21-31	D11662		11		SM00809		S		YC051-YL999, YR301-YR328
0810K	18		PA		8-0	33-27-32	D11662		10		SM00810		S		YC051-YL999, YR301-YR328
0811WY	18		PA		8-11	33-25-32	D11664		1		SM00821		S		YC051-YL999, YR301-YR328
0811WY	18		PA		7-4	33-25-32	D11664		1		SM00821		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W4250

Page 35

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
0812WV	22		PA		8-11	33-27-32		D11664		2		SM00822		S		YC051-YL999, YR301-YR328
0812WV	22		PA		7-3	33-27-32		D11664		2		SM00822		S		YN231-YN501
0813WG	22		PA		8-11	33-27-32		D11664		3		SM00823		S		YC051-YL999, YR301-YR328
0813WG	22		PA		7-3	33-27-32		D11664		3		SM00823		S		YN231-YN501
0814WO	22		PA		8-11	33-27-32		D11664		4		SM00824		S		YC051-YL999, YR301-YR328
0814WO	22		PA		7-3	33-27-32		D11664		4		SM00824		S		YN231-YN501
0815V	22		PA		8-11	33-27-32		D11664		5		SM00825		S		YC051-YL999, YR301-YR328
0815V	22		PA		7-3	33-27-32		D11664		5		SM00825		S		YN231-YN501
0816N	18		PA		8-11	33-23-22		D11664		6		SM00826		S		YC051-YL999, YR301-YR328
0816N	18		PA		7-4	33-23-22		D11664		6		SM00826		S		YN231-YN501
0817W	20		PA		8-11	33-25-32		D11664		7		SM00827		S		YC051-YL999, YR301-YR328
0817W	20		PA		7-4	33-25-32		D11664		7		SM00827		S		YN231-YN501
0818O	18		PA		8-11	33-23-22		D11664		8		SM00828		S		YC051-YL999, YR301-YR328
0818O	18		PA		7-4	33-23-22		D11664		8		SM00828		S		YN231-YN501
0819A	16		CQ		8-11	35-21-31		D11664		11		SM00829		S		YC051-YL999, YR301-YR328
0819A	16		CQ		7-3	35-21-31		D11664		11		SM00829		S		YN231-YN501
0820K	18		PA		8-11	33-27-32		D11664		10		SM00830		S		YC051-YL999, YR301-YR328
0820K	18		PA		7-3	33-27-32		D11664		10		SM00830		S		YN231-YN501
0821WY	18		PA		8-0	33-25-32		D11666		1		SM00821		S		YC051-YL999, YR301-YR328
0821WY	18		PA		9-4	33-25-32		D11666		1		SM00821		S		YN231-YN501
0822WV	22		PA		8-0	33-27-32		D11666		2		SM00822		S		YC051-YL999, YR301-YR328
0822WV	22		PA		9-5	33-27-32		D11666		2		SM00822		S		YN231-YN501
0823WG	22		PA		8-0	33-27-32		D11666		3		SM00823		S		YC051-YL999, YR301-YR328
0823WG	22		PA		9-5	33-27-32		D11666		3		SM00823		S		YN231-YN501
0824WO	22		PA		8-0	33-27-32		D11666		4		SM00824		S		YC051-YL999, YR301-YR328
0824WO	22		PA		9-5	33-27-32		D11666		4		SM00824		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W4250

Page 36

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W4250	286A4250			P18 AND AB0340B DISC TO RIGHT PSU'S (continued)										
0825V	22		PA	8-0	33-27-32	D11666		5		SM00825		S		YC051-YL999, YR301-YR328
0825V	22		PA	9-5	33-27-32	D11666		5		SM00825		S		YN231-YN501
0826N	18		PA	8-0	33-23-22	D11666		6		SM00826		S		YC051-YL999, YR301-YR328
0826N	18		PA	9-4	33-23-22	D11666		6		SM00826		S		YN231-YN501
0827W	20		PA	8-0	33-25-32	D11666		7		SM00827		S		YC051-YL999, YR301-YR328
0827W	20		PA	9-4	33-25-32	D11666		7		SM00827		S		YN231-YN501
0828O	18		PA	8-0	33-23-22	D11666		8		SM00828		S		YC051-YL999, YR301-YR328
0828O	18		PA	9-4	33-23-22	D11666		8		SM00828		S		YN231-YN501
0829A	16		CQ	8-0	35-21-31	D11666		11		SM00829		S		YC051-YL999, YR301-YR328
0829A	16		CQ	9-5	35-21-31	D11666		11		SM00829		S		YN231-YN501
0830K	18		PA	8-0	33-27-32	D11666		10		SM00830		S		YC051-YL999, YR301-YR328
0830K	18		PA	9-5	33-27-32	D11666		10		SM00830		S		YN231-YN501
0831WY	18		PA	8-9	33-25-32	D11668		1		SM00841		S		YC051-YL999, YR301-YR328
0831WY	18		PA	10-1	33-25-32	D11668		1		SM00841		S		YN231-YN501
0832WV	22		PA	8-9	33-27-32	D11668		2		SM00842		S		YC051-YL999, YR301-YR328
0832WV	22		PA	10-2	33-27-32	D11668		2		SM00842		S		YN231-YN501
0833WG	22		PA	8-9	33-27-32	D11668		3		SM00843		S		YC051-YL999, YR301-YR328
0833WG	22		PA	10-2	33-27-32	D11668		3		SM00843		S		YN231-YN501
0834WO	22		PA	8-9	33-27-32	D11668		4		SM00844		S		YC051-YL999, YR301-YR328
0834WO	22		PA	10-2	33-27-32	D11668		4		SM00844		S		YN231-YN501
0835V	22		PA	8-9	33-27-32	D11668		5		SM00845		S		YC051-YL999, YR301-YR328
0835V	22		PA	10-2	33-27-32	D11668		5		SM00845		S		YN231-YN501
0836N	18		PA	8-9	33-23-22	D11668		6		SM00846		S		YC051-YL999, YR301-YR328
0836N	18		PA	10-1	33-23-22	D11668		6		SM00846		S		YN231-YN501
0837W	20		PA	8-9	33-25-32	D11668		7		SM00847		S		YC051-YL999, YR301-YR328
0837W	20		PA	10-1	33-25-32	D11668		7		SM00847		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W4250

Page 37

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)										
0838O	18		PA		8-9	33-23-22	D11668		8		SM00848		S		YC051-YL999, YR301-YR328
0838O	18		PA		10-1	33-23-22	D11668		8		SM00848		S		YN231-YN501
0839A	16		CQ		8-9	35-21-31	D11668		11		SM00849		S		YC051-YL999, YR301-YR328
0839A	16		CQ		10-2	35-21-31	D11668		11		SM00849		S		YN231-YN501
0840K	18		PA		8-9	33-27-32	D11668		10		SM00850		S		YC051-YL999, YR301-YR328
0840K	18		PA		10-2	33-27-32	D11668		10		SM00850		S		YN231-YN501
0841WY	18		PA		8-0	33-25-32	D11670		1		SM00841		S		YC051-YL999, YR301-YR328
0841WY	18		PA		11-0	33-25-32	D11670		1		SM00841		S		YN231-YN501
0842WV	22		PA		8-0	33-27-32	D11670		2		SM00842		S		YC051-YL999, YR301-YR328
0842WV	22		PA		11-0	33-27-32	D11670		2		SM00842		S		YN231-YN501
0843WG	22		PA		8-0	33-27-32	D11670		3		SM00843		S		YC051-YL999, YR301-YR328
0843WG	22		PA		11-0	33-27-32	D11670		3		SM00843		S		YN231-YN501
0844WO	22		PA		8-0	33-27-32	D11670		4		SM00844		S		YC051-YL999, YR301-YR328
0844WO	22		PA		11-0	33-27-32	D11670		4		SM00844		S		YN231-YN501
0845V	22		PA		8-0	33-27-32	D11670		5		SM00845		S		YC051-YL999, YR301-YR328
0845V	22		PA		11-0	33-27-32	D11670		5		SM00845		S		YN231-YN501
0846N	18		PA		8-0	33-23-22	D11670		6		SM00846		S		YC051-YL999, YR301-YR328
0846N	18		PA		11-0	33-23-22	D11670		6		SM00846		S		YN231-YN501
0847W	20		PA		8-0	33-25-32	D11670		7		SM00847		S		YC051-YL999, YR301-YR328
0847W	20		PA		11-0	33-25-32	D11670		7		SM00847		S		YN231-YN501
0848O	18		PA		8-0	33-23-22	D11670		8		SM00848		S		YC051-YL999, YR301-YR328
0848O	18		PA		11-0	33-23-22	D11670		8		SM00848		S		YN231-YN501
0849A	16		CQ		8-0	35-21-31	D11670		11		SM00849		S		YC051-YL999, YR301-YR328
0849A	16		CQ		11-0	35-21-31	D11670		11		SM00849		S		YN231-YN501
0850K	18		PA		8-0	33-27-32	D11670		10		SM00850		S		YC051-YL999, YR301-YR328
0850K	18		PA		11-0	33-27-32	D11670		10		SM00850		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W4250

Page 38

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)										
0851WY	18		PA		8-8	33-25-32	D11672		1			SM00861		S	YC051-YL999, YR301-YR328
0851WY	18		PA		11-6	33-25-32	D11672		1			SM00861		S	YN231-YN501
0852WV	22		PA		8-8	33-27-32	D11672		2			SM00862		S	YC051-YL999, YR301-YR328
0852WV	22		PA		11-7	33-27-32	D11672		2			SM00862		S	YN231-YN501
0853WG	22		PA		8-8	33-27-32	D11672		3			SM00863		S	YC051-YL999, YR301-YR328
0853WG	22		PA		11-7	33-27-32	D11672		3			SM00863		S	YN231-YN501
0854WO	22		PA		8-8	33-27-32	D11672		4			SM00864		S	YC051-YL999, YR301-YR328
0854WO	22		PA		11-7	33-27-32	D11672		4			SM00864		S	YN231-YN501
0855V	22		PA		8-8	33-27-32	D11672		5			SM00865		S	YC051-YL999, YR301-YR328
0855V	22		PA		11-7	33-27-32	D11672		5			SM00865		S	YN231-YN501
0856N	18		PA		8-8	33-23-22	D11672		6			SM00866		S	YC051-YL999, YR301-YR328
0856N	18		PA		11-6	33-23-22	D11672		6			SM00866		S	YN231-YN501
0857W	20		PA		8-8	33-25-32	D11672		7			SM00867		S	YC051-YL999, YR301-YR328
0857W	20		PA		11-6	33-25-32	D11672		7			SM00867		S	YN231-YN501
0858O	18		PA		8-8	33-23-22	D11672		8			SM00868		S	YC051-YL999, YR301-YR328
0858O	18		PA		11-6	33-23-22	D11672		8			SM00868		S	YN231-YN501
0859A	16		CQ		8-8	35-21-31	D11672		11			SM00869		S	YC051-YL999, YR301-YR328
0859A	16		CQ		11-7	35-21-31	D11672		11			SM00869		S	YN231-YN501
0860K	18		PA		8-8	33-27-32	D11672		10			SM00870		S	YC051-YL999, YR301-YR328
0860K	18		PA		11-7	33-27-32	D11672		10			SM00870		S	YN231-YN501
0861WY	18		PA		7-9	33-25-32	D11674		1			SM00861		S	YC051-YL999, YR301-YR328
0862WV	22		PA		7-9	33-27-32	D11674		2			SM00862		S	YC051-YL999, YR301-YR328
0863WG	22		PA		7-9	33-27-32	D11674		3			SM00863		S	YC051-YL999, YR301-YR328
0864WO	22		PA		7-9	33-27-32	D11674		4			SM00864		S	YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 39

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)										
0865V	22		PA		7-9	33-27-32	D11674		5		SM00865		S		YC051-YL999, YR301-YR328
0866N	18		PA		7-9	33-23-22	D11674		6		SM00866		S		YC051-YL999, YR301-YR328
0867W	20		PA		7-9	33-25-32	D11674		7		SM00867		S		YC051-YL999, YR301-YR328
0868O	18		PA		7-9	33-23-22	D11674		8		SM00868		S		YC051-YL999, YR301-YR328
0869A	16		CQ		7-9	35-21-31	D11674		11		SM00869		S		YC051-YL999, YR301-YR328
0870K	18		PA		7-9	33-27-32	D11674		10		SM00870		S		YC051-YL999, YR301-YR328
0871WY	18		PA		8-6	33-25-32	D11676		1		SM00881		S		YC051-YL999, YR301-YR328
0871WY	18		PA		11-1	33-25-32	D11676		1		SM00861		S		YN231-YN501
0872WV	22		PA		8-6	33-27-32	D11676		2		SM00882		S		YC051-YL999, YR301-YR328
0872WV	22		PA		11-2	33-27-32	D11676		2		SM00862		S		YN231-YN501
0873WG	22		PA		8-6	33-27-32	D11676		3		SM00883		S		YC051-YL999, YR301-YR328
0873WG	22		PA		11-2	33-27-32	D11676		3		SM00863		S		YN231-YN501
0874WO	22		PA		8-6	33-27-32	D11676		4		SM00884		S		YC051-YL999, YR301-YR328
0874WO	22		PA		11-2	33-27-32	D11676		4		SM00864		S		YN231-YN501
0875V	22		PA		8-6	33-27-32	D11676		5		SM00885		S		YC051-YL999, YR301-YR328
0875V	22		PA		11-2	33-27-32	D11676		5		SM00865		S		YN231-YN501
0876N	18		PA		8-6	33-23-22	D11676		6		SM00886		S		YC051-YL999, YR301-YR328
0876N	18		PA		11-1	33-23-22	D11676		6		SM00866		S		YN231-YN501
0877W	20		PA		8-6	33-25-32	D11676		7		SM00887		S		YC051-YL999, YR301-YR328
0877W	20		PA		11-1	33-25-32	D11676		7		SM00867		S		YN231-YN501
0878O	18		PA		8-6	33-23-22	D11676		8		SM00888		S		YC051-YL999, YR301-YR328
0878O	18		PA		11-1	33-23-22	D11676		8		SM00868		S		YN231-YN501
0879A	16		CQ		8-6	35-21-31	D11676		11		SM00889		S		YC051-YL999, YR301-YR328
0879A	16		CQ		11-2	35-21-31	D11676		11		SM00869		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W4250

Page 40

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250			P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
0880K	18		PA		8-6	33-27-32	D11676	10			SM00890		S		YC051-YL999, YR301-YR328
0880K	18		PA		11-2	33-27-32	D11676	10			SM00870		S		YN231-YN501
0881WY	18		PA		7-6	33-25-32	D11678	1			SM00881		S		YC051-YL999, YR301-YR328
0881WY	18		PA		11-6	33-25-32	D11678	1			SM00861		S		YN231-YN501
0882WV	22		PA		7-6	33-27-32	D11678	2			SM00882		S		YC051-YL999, YR301-YR328
0882WV	22		PA		11-7	33-27-32	D11678	2			SM00862		S		YN231-YN501
0883WG	22		PA		7-6	33-27-32	D11678	3			SM00883		S		YC051-YL999, YR301-YR328
0883WG	22		PA		11-7	33-27-32	D11678	3			SM00863		S		YN231-YN501
0884WO	22		PA		7-6	33-27-32	D11678	4			SM00884		S		YC051-YL999, YR301-YR328
0884WO	22		PA		11-7	33-27-32	D11678	4			SM00864		S		YN231-YN501
0885V	22		PA		7-6	33-27-32	D11678	5			SM00885		S		YC051-YL999, YR301-YR328
0885V	22		PA		11-7	33-27-32	D11678	5			SM00865		S		YN231-YN501
0886N	18		PA		7-6	33-23-22	D11678	6			SM00886		S		YC051-YL999, YR301-YR328
0886N	18		PA		11-6	33-23-22	D11678	6			SM00866		S		YN231-YN501
0887W	20		PA		7-6	33-25-32	D11678	7			SM00887		S		YC051-YL999, YR301-YR328
0887W	20		PA		11-6	33-25-32	D11678	7			SM00867		S		YN231-YN501
0888O	18		PA		7-6	33-23-22	D11678	8			SM00888		S		YC051-YL999, YR301-YR328
0888O	18		PA		11-6	33-23-22	D11678	8			SM00868		S		YN231-YN501
0889A	16		CQ		7-6	35-21-31	D11678	11			SM00889		S		YC051-YL999, YR301-YR328
0889A	16		CQ		11-7	35-21-31	D11678	11			SM00869		S		YN231-YN501
0890K	18		PA		7-6	33-27-32	D11678	10			SM00890		S		YC051-YL999, YR301-YR328
0890K	18		PA		11-7	33-27-32	D11678	10			SM00870		S		YN231-YN501
0901	20		PA		95-2	SPARE	D40298P	1			D40272P	2			YC051-YC052
0901	20		PA		95-8	SPARE	D40298P	1			D40272P	2			YC053-YL999, YR301-YR328
0901	20		PA		76-3	SPARE	D40298P	1			D40272P	2			YN231-YN501
0903	20		PA		95-2	SPARE	D40298P	3			D40272P	8			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W4250

Page 41

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY	Description Fam FT-IN Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W4250	286A4250	P18 AND AB0340B DISC TO RIGHT PSU'S (continued)									
0903	20	PA	95-8	SPARE	D40298P	3	D40272P	8			YC053-YL999, YR301-YR328
0903	20	PA	76-3	SPARE	D40298P	3	D40272P	8			YN231-YN501
0904	20	PA	95-2	SPARE	D40298P	4	D40272P	9			YC051-YC052
0904	20	PA	95-8	SPARE	D40298P	4	D40272P	9			YC053-YL999, YR301-YR328
0904	20	PA	76-3	SPARE	D40298P	4	D40272P	9			YN231-YN501
0907	20	PA	8-6	33-25-32	D40298P	7	D40084P	7			YC051-YC052
0907	20	PA	9-0	33-25-32	D40298P	7	D40084P	7			YC053-YR328
0908	20	PA	8-6	33-25-31	D40298P	8	D40084P	8			YC051-YC052
0908	20	PA	9-0	33-25-31	D40298P	8	D40084P	8			YC053-YR328
0909	18	PA	8-6	33-25-32	D40298P	9	D40084P	9			YC051-YC052
0909	18	PA	9-0	33-25-32	D40298P	9	D40084P	9			YC053-YR328
0911	22	PA	11-10	33-27-31	D40298P	11	SM00505		S		YC051-YC052
0911	22	PA	12-4	33-27-31	D40298P	11	SM00505		S		YC053-YL999, YR301-YR328
0911	22	PA	12-2	33-27-31	D40298P	11	SM00505		S		YN231-YN501
0912	22	PA	11-10	33-27-31	D40298P	12	SM00502		S		YC051-YC052
0912	22	PA	12-4	33-27-31	D40298P	12	SM00502		S		YC053-YL999, YR301-YR328
0912	22	PA	12-2	33-27-31	D40298P	12	SM00502		S		YN231-YN501
0913	22	PA	11-10	33-27-31	D40298P	13	SM00503		S		YC051-YC052
0913	22	PA	12-4	33-27-31	D40298P	13	SM00503		S		YC053-YL999, YR301-YR328
0913	22	PA	12-2	33-27-31	D40298P	13	SM00503		S		YN231-YN501
0914	22	PA	11-10	33-27-31	D40298P	14	SM00504		S		YC051-YC052
0914	22	PA	12-4	33-27-31	D40298P	14	SM00504		S		YC053-YL999, YR301-YR328
0914	22	PA	12-2	33-27-31	D40298P	14	SM00504		S		YN231-YN501
0915	16	CQ	11-10	35-21-31	D40298P	15	SM00409		S		YC051-YC052
0915	16	CQ	12-4	35-21-31	D40298P	15	SM00409		S		YC053-YL999, YR301-YR328
0915	16	CQ	12-2	35-21-31	D40298P	15	SM00409		S		YN231-YN501
0916	16	CQ	57-6	35-21-31	D40298P	16	SM00749		S		YC051-YC052
0916	16	CQ	58-0	35-21-31	D40298P	16	SM00749		S		YC053-YL999, YR301-YR328
0916	16	CQ	47-11	35-21-31	D40298P	16	SM00709		S		YN231-YN501
0919	18	PA	8-6	33-25-31	D40298P	19	D40084P	10			YC051-YC052
0919	18	PA	9-0	33-25-31	D40298P	19	D40084P	10			YC053-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 42

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W4250	286A4250	P18 AND AB0340B DISC TO RIGHT PSU'S (continued)													
0921	20	PA	6-11	33-25-31	D40072P	1			SM00507		S		YC051-YL999, YR301-YR328		
0921	20	PA	7-0	33-25-31	D40072P	1			SM00507		S		YN231-YN501		
0922	18	PA	6-11	33-25-31	D40072P	2			SM00501		S		YC051-YL999, YR301-YR328		
0922	18	PA	7-0	33-25-31	D40072P	2			SM00501		S		YN231-YN501		
0924	18	PA	2-10	33-27-31	SM00590		S		GD03868	DC..	1		ALL		
0925	18	PA	1-10	33-27-32	SM00750		S		GD04008	DC..	1		YC051-YL999, YR301-YR328		
0925	18	PA	2-9	33-27-32	SM00710		S		GD04008	DC..	1		YN231-YN501		
0926	18	PA	3-11	33-27-32	SM00890		S		GD04002	DC..	1		YC051-YL999, YR301-YR328		
0926	18	PA	2-4	33-27-32	SM00850		S		GD04002	DC..	1		YN231-YN501		
0931	18	PA	4-5	33-25-31	D40204J	16			SM00501		S		YC051-YL999		
0931	18	PA	4-6	33-25-31	D40204J	16			SM00501		S		YN231-YN260		
0931	18	PA	6-11	33-25-31	D40205J	16			SM00501		S		YN501		
0931	18	PA	7-2	33-25-31	D40205J	16			SM00501		S		YR301-YR328		
0937	20	PA	4-5	33-25-31	D40204J	7			SM00507		S		YC051-YL999		
0937	20	PA	4-6	33-25-31	D40204J	7			SM00507		S		YN231-YN260		
0937	20	PA	6-11	33-25-31	D40205J	7			SM00507		S		YN501		
0937	20	PA	7-2	33-25-31	D40205J	7			SM00507		S		YR301-YR328		
0939	16	CQ	0-7	35-21-31	SM00409		S		SM00509		S		ALL		
0941	18	PA	6-4	33-25-32	D40206J	16			SM00741		S		YC051-YL999		
0941	18	PA	7-0	33-25-32	D40206J	16			SM00701		S		YN231-YN260		
0941	18	PA	6-6	33-25-32	D40207J	16			SM00701		S		YN501		
0941	18	PA	5-5	33-25-32	D40207J	16			SM00741		S		YR301-YR328		
0947	20	PA	6-4	33-25-32	D40206J	15			SM00747		S		YC051-YL999		
0947	20	PA	7-0	33-25-32	D40206J	15			SM00707		S		YN231-YN260		
0947	20	PA	6-6	33-25-32	D40207J	15			SM00707		S		YN501		
0947	20	PA	5-5	33-25-32	D40207J	15			SM00747		S		YR301-YR328		
0950	16	CQ	4-9	35-21-31	SM00949		S		D40272P		16		YC051-YL999, YR301-YR328		
0950	16	CQ	5-4	35-21-31	SM00869		S		D40272P		16		YN231-YN501		
0951	20	PA	4-9	33-25-32	D40272P	1			SM00947		S		YC051-YL999, YR301-YR328		
0951	20	PA	5-4	33-25-32	D40272P	1			SM00867		S		YN231-YN501		
0952	22	PA	4-9	33-27-32	SM00942		S		D40272P		10		YC051-YL999, YR301-YR328		
0952	22	PA	5-4	33-27-32	SM00862		S		D40272P		10		YN231-YN501		

WIRE LIST

D280A108

91-21-11

Section W4250

Page 43

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250			P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
0953	22		PA		4-9	33-27-32	SM00943		S		D40272P	11			YC051-YL999, YR301-YR328
0953	22		PA		5-4	33-27-32	SM00863		S		D40272P	11			YN231-YN501
0955	22		PA		4-9	33-27-32	SM00945		S		D40272P	5			YC051-YL999, YR301-YR328
0955	22		PA		5-4	33-27-32	SM00865		S		D40272P	5			YN231-YN501
0957	18		PA		4-9	33-25-32	D40272P	6			SM00941		S		YC051-YL999, YR301-YR328
0957	18		PA		5-4	33-25-32	D40272P	6			SM00861		S		YN231-YN501
2001B	22		PB	GA	8-7	23-31-03	D11600	14			SM00514		S		YC051-YL999, YR301-YR328
2001B	22		PB	GA	7-2	23-31-03	D11600	14			SM00514		S		YN231-YN501
2001R	22		PB	GA	0-0	23-31-03	D11600	13			SM00513		S		ALL
2011B	22		PB	GK	9-10	23-31-03	D11602	14			SM00514		S		YC051-YL999, YR301-YR328
2011B	22		PB	GK	10-1	23-31-03	D11602	14			SM00514		S		YN231-YN501
2011R	22		PB	GK	0-0	23-31-03	D11602	13			SM00513		S		ALL
2013B	22		PB	GM	5-3	23-31-03	SM00514		S		SM00534		S		YC051-YL999, YR301-YR328
2013B	22		PB	GM	2-3	23-31-03	SM00514		S		SM00534		S		YN231-YN501
2013R	22		PB	GM	0-0	23-31-03	SM00513		S		SM00533		S		ALL
2021B	22		PB	GV	9-7	23-31-03	D11604	14			SM00534		S		YC051-YL999
2021B	22		PB	GV	9-0	23-31-03	D11604	14			SM00534		S		YN231-YN501
2021B	22		PB	GV	9-5	23-31-03	D11604	14			SM00534		S		YR301-YR328
2021R	22		PB	GV	0-0	23-31-03	D11604	13			SM00533		S		ALL
2031B	22		PB	HF	7-3	23-31-03	D11606	14			SM00534		S		YC051-YL999, YR301-YR328
2031B	22		PB	HF	6-11	23-31-03	D11606	14			SM00534		S		YN231-YN501
2031R	22		PB	HF	0-0	23-31-03	D11606	13			SM00533		S		ALL
2033B	22		PB	HH	2-5	23-31-03	SM00534		S		SM00554		S		YC051-YL999, YR301-YR328
2033B	22		PB	HH	3-9	23-31-03	SM00534		S		SM00554		S		YN231-YN501
2033R	22		PB	HH	0-0	23-31-03	SM00533		S		SM00553		S		ALL
2041B	22		PB	HQ	7-7	23-31-03	D11608	14			SM00554		S		YC051-YL999, YR301-YR328
2041B	22		PB	HQ	7-0	23-31-03	D11608	14			SM00554		S		YN231-YN501
2041R	22		PB	HQ	0-0	23-31-03	D11608	13			SM00553		S		ALL
2051B	22		PB	IA	9-8	23-31-03	D11610	14			SM00554		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11
Section W4250
Page 44
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W4250	286A4250	P18 AND AB0340B DISC TO RIGHT PSU'S (continued)													
2051B	22	PB	IA	7-0	23-31-03	D11610	14		SM00554		S		YN231-YN501		
2051R	22	PB	IA	0-0	23-31-03	D11610	13		SM00553		S		ALL		
2053B	22	PB	IC	6-1	23-31-03	SM00554		S	SM00574		S		YC051-YL999, YR301-YR328		
2053B	22	PB	IC	5-4	23-31-03	SM00554		S	SM00574		S		YN231-YN501		
2053R	22	PB	IC	0-0	23-31-03	SM00553		S	SM00573		S		ALL		
2061B	22	PB	IK	8-7	23-31-03	D11612	14		SM00574		S		YC051-YL999, YR301-YR328		
2061B	22	PB	IK	7-6	23-31-03	D11612	14		SM00574		S		YN231-YN501		
2061R	22	PB	IK	0-0	23-31-03	D11612	13		SM00573		S		ALL		
2071B	22	PB	IV	8-0	23-31-03	D11614	14		SM00574		S		YC051-YL999, YR301-YR328		
2071B	22	PB	IV	9-0	23-31-03	D11614	14		SM00574		S		YN231-YN501		
2071R	22	PB	IV	0-0	23-31-03	D11614	13		SM00573		S		ALL		
2073B	22	PB	IX	4-3	23-31-03	SM00574		S	SM00594		S		YC051-YL999, YR301-YR328		
2073B	22	PB	IX	6-6	23-31-03	SM00574		S	SM00594		S		YN231-YN501		
2073R	22	PB	IX	0-0	23-31-03	SM00573		S	SM00593		S		ALL		
2081B	22	PB	JF	8-10	23-31-03	D11616	14		SM00594		S		YC051-YL999, YR301-YR328		
2081B	22	PB	JF	8-7	23-31-03	D11616	14		SM00594		S		YN231-YN501		
2081R	22	PB	JF	0-0	23-31-03	D11616	13		SM00593		S		ALL		
2091B	22	PB	JQ	8-1	23-31-03	D11618	14		SM00594		S		YC051-YL999, YR301-YR328		
2091B	22	PB	JQ	9-2	23-31-03	D11618	14		SM00594		S		YN231-YN501		
2091R	22	PB	JQ	0-0	23-31-03	D11618	13		SM00593		S		ALL		
2093B	22	PB	JS	4-1	23-31-03	SM00594		S	SM00614		S		YC051-YL999, YR301-YR328		
2093B	22	PB	JS	7-2	23-31-03	SM00594		S	SM00654		S		YN231-YN501		
2093R	22	PB	JS	0-0	23-31-03	SM00593		S	SM00613		S		YC051-YL999, YR301-YR328		
2093R	22	PB	JS	0-0	23-31-03	SM00593		S	SM00653		S		YN231-YN501		
2201B	22	PB	KA	8-10	23-31-03	D11620	14		SM00614		S		YC051-YL999, YR301-YR328		
2201B	22	PB	KA	11-7	23-31-03	D11620	14		SM00654		S		YN231-YN501		
2201R	22	PB	KA	0-0	23-31-03	D11620	13		SM00613		S		YC051-YL999, YR301-YR328		
2201R	22	PB	KA	0-0	23-31-03	D11620	13		SM00653		S		YN231-YN501		

WIRE LIST

D280A108

91-21-11

Section W4250

Page 45

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)										
2211B	22	PB	KK		8-1	23-31-03	D11622	14			SM00614		S		YC051-YL999, YR301-YR328
2211R	22	PB	KK		0-0	23-31-03	D11622	13			SM00613		S		YC051-YL999, YR301-YR328
2213B	22	PB	KM		4-2	23-31-03	SM00614		S		SM00634		S		YC051-YL999, YR301-YR328
2213R	22	PB	KM		0-0	23-31-03	SM00613		S		SM00633		S		YC051-YL999, YR301-YR328
2221B	22	PB	KV		8-7	23-31-03	D11624	14			SM00634		S		YC051-YL999, YR301-YR328
2221R	22	PB	KV		0-0	23-31-03	D11624	13			SM00633		S		YC051-YL999, YR301-YR328
2231B	22	PB	LF		7-3	23-31-03	D11626	14			SM00634		S		YC051-YL999, YR301-YR328
2231R	22	PB	LF		0-0	23-31-03	D11626	13			SM00633		S		YC051-YL999, YR301-YR328
2233B	22	PB	LH		2-6	23-31-03	SM00634		S		SM00654		S		YC051-YL999, YR301-YR328
2233R	22	PB	LH		0-0	23-31-03	SM00633		S		SM00653		S		YC051-YL999, YR301-YR328
2241B	22	PB	LQ		7-11	23-31-03	D11628	14			SM00654		S		YC051-YL999, YR301-YR328
2241R	22	PB	LQ		0-0	23-31-03	D11628	13			SM00653		S		YC051-YL999, YR301-YR328
2251B	22	PB	MA		10-10	23-31-03	D11630	14			SM00654		S		YC051-YL999, YR301-YR328
2251B	22	PB	MA		8-6	23-31-03	D11630	14			SM00654		S		YN231-YN501
2251R	22	PB	MA		0-0	23-31-03	D11630	13			SM00653		S		ALL
2253B	22	PB	MC		6-8	23-31-03	SM00654		S		SM00674		S		YC051-YL999, YR301-YR328
2253B	22	PB	MC		6-3	23-31-03	SM00654		S		SM00674		S		YN231-YN501
2253R	22	PB	MC		0-0	23-31-03	SM00653		S		SM00673		S		ALL
2261B	22	PB	MK		6-8	23-31-03	D11632	14			SM00674		S		YC051-YL999, YR301-YR328
2261B	22	PB	MK		9-0	23-31-03	D11632	14			SM00654		S		YN231-YN501
2261R	22	PB	MK		0-0	23-31-03	D11632	13			SM00673		S		YC051-YL999, YR301-YR328
2261R	22	PB	MK		0-0	23-31-03	D11632	13			SM00653		S		YN231-YN501

WIRE LIST

D280A108

91-21-11
Section W4250
Page 46
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250			P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
2271B	22		PB	MV	7-3	23-31-03	D11634	14			SM00674		S		YC051-YL999, YR301-YR328
2271B	22		PB	MV	8-2	23-31-03	D11634	14			SM00674		S		YN231-YN501
2271R	22		PB	MV	0-0	23-31-03	D11634	13			SM00673		S		ALL
2273B	22		PB	MX	3-8	23-31-03	SM00674			S	SM00694		S		YC051-YL999, YR301-YR328
2273B	22		PB	MX	4-5	23-31-03	SM00674			S	SM00694		S		YN231-YN501
2273R	22		PB	MX	0-0	23-31-03	SM00673			S	SM00693		S		ALL
2281B	22		PB	NF	7-11	23-31-03	D11636	14			SM00694		S		YC051-YL999, YR301-YR328
2281B	22		PB	NF	7-6	23-31-03	D11636	14			SM00674		S		YN231-YN501
2281R	22		PB	NF	0-0	23-31-03	D11636	13			SM00693		S		YC051-YL999, YR301-YR328
2281R	22		PB	NF	0-0	23-31-03	D11636	13			SM00673		S		YN231-YN501
2291B	22		PB	NQ	7-4	23-31-03	D11638	14			SM00694		S		YC051-YL999, YR301-YR328
2291B	22		PB	NQ	8-8	23-31-03	D11638	14			SM00694		S		YN231-YN501
2291R	22		PB	NQ	0-0	23-31-03	D11638	13			SM00693		S		ALL
2293B	22		PB	NS	5-1	23-31-03	SM00694			S	SM00714		S		YC051-YL999, YR301-YR328
2293B	22		PB	NS	6-6	23-31-03	SM00694			S	SM00714		S		YN231-YN501
2293R	22		PB	NS	0-0	23-31-03	SM00693			S	SM00713		S		ALL
2401B	22		PB	OA	9-0	23-31-03	D11640	14			SM00714		S		YC051-YL999, YR301-YR328
2401B	22		PB	OA	7-7	23-31-03	D11640	14			SM00694		S		YN231-YN501
2401R	22		PB	OA	0-0	23-31-03	D11640	13			SM00713		S		YC051-YL999, YR301-YR328
2401R	22		PB	OA	0-0	23-31-03	D11640	13			SM00693		S		YN231-YN501
2411B	22		PB	OK	7-7	23-31-03	D11642	14			SM00714		S		YC051-YL999, YR301-YR328
2411B	22		PB	OK	7-2	23-31-03	D11642	14			SM00714		S		YN231-YN501
2411R	22		PB	OK	0-0	23-31-03	D11642	13			SM00713		S		ALL
2413B	22		PB	OM	2-8	23-31-03	SM00714			S	SM00734		S		YC051-YL999, YR301-YR328
2413B	22		PB	OM	6-0	23-31-03	SM00714			S	SM00734		S		YN231-YN501
2413R	22		PB	OM	0-0	23-31-03	SM00713			S	SM00733		S		ALL
2421B	22		PB	OV	8-4	23-31-03	D11644	14			SM00734		S		YC051-YL999, YR301-YR328
2421B	22		PB	OV	10-7	23-31-03	D11644	14			SM00714		S		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W4250

Page 47

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)										
2421R	22	PB	OV		0-0	23-31-03	D11644	13			SM00733		S		YC051-YL999, YR301-YR328
2421R	22	PB	OV		0-0	23-31-03	D11644	13			SM00713		S		YN231-YN501
2431B	22	PB	PF		10-4	23-31-03	D11646	14			SM00734		S		YC051-YL999, YR301-YR328
2431B	22	PB	PF		11-2	23-31-03	D11646	14			SM00734		S		YN231-YN501
2431R	22	PB	PF		0-0	23-31-03	D11646	13			SM00733		S		ALL
2433B	22	PB	PH		6-6	23-31-03	SM00734		S		SM00754		S		YC051-YL999, YR301-YR328
2433B	22	PB	PH		6-1	23-31-03	SM00734		S		SM00754		S		YN231-YN501
2433R	22	PB	PH		0-0	23-31-03	SM00733		S		SM00753		S		ALL
2441B	22	PB	PQ		9-0	23-31-03	D11648	14			SM00754		S		YC051-YL999, YR301-YR328
2441B	22	PB	PQ		10-4	23-31-03	D11648	14			SM00734		S		YN231-YN501
2441R	22	PB	PQ		0-0	23-31-03	D11648	13			SM00753		S		YC051-YL999, YR301-YR328
2441R	22	PB	PQ		0-0	23-31-03	D11648	13			SM00733		S		YN231-YN501
2451B	22	PB	QA		8-3	23-31-03	D11650	14			SM00754		S		YC051-YL999, YR301-YR328
2451B	22	PB	QA		8-8	23-31-03	D11650	14			SM00754		S		YN231-YN501
2451R	22	PB	QA		0-0	23-31-03	D11650	13			SM00753		S		ALL
2453B	22	PB	QC		4-0	23-31-03	SM00754		S		SM00774		S		YC051-YL999, YR301-YR328
2453B	22	PB	QC		3-11	23-31-03	SM00754		S		SM00834		S		YN231-YN501
2453R	22	PB	QC		0-0	23-31-03	SM00753		S		SM00773		S		YC051-YL999, YR301-YR328
2453R	22	PB	QC		0-0	23-31-03	SM00753		S		SM00833		S		YN231-YN501
2461B	22	PB	QK		8-5	23-31-03	D11652	14			SM00774		S		YC051-YL999, YR301-YR328
2461B	22	PB	QK		10-8	23-31-03	D11652	14			SM00754		S		YN231-YN501
2461R	22	PB	QK		0-0	23-31-03	D11652	13			SM00773		S		YC051-YL999, YR301-YR328
2461R	22	PB	QK		0-0	23-31-03	D11652	13			SM00753		S		YN231-YN501
2471B	22	PB	QV		7-6	23-31-03	D11654	14			SM00774		S		YC051-YL999, YR301-YR328
2471R	22	PB	QV		0-0	23-31-03	D11654	13			SM00773		S		YC051-YL999, YR301-YR328
2473B	22	PB	QX		3-11	23-31-03	SM00774		S		SM00794		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 48

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)										
2473R	22	PB	QX		0-0	23-31-03	SM00773		S		SM00793		S		YC051-YL999, YR301-YR328
2481B	22	PB	RF		8-7	23-31-03	D11656	14			SM00794		S		YC051-YL999, YR301-YR328
2481R	22	PB	RF		0-0	23-31-03	D11656	13			SM00793		S		YC051-YL999, YR301-YR328
2491B	22	PB	RQ		7-11	23-31-03	D11658	14			SM00794		S		YC051-YL999, YR301-YR328
2491R	22	PB	RQ		0-0	23-31-03	D11658	13			SM00793		S		YC051-YL999, YR301-YR328
2493B	22	PB	RS		4-5	23-31-03	SM00794		S		SM00814		S		YC051-YL999, YR301-YR328
2493R	22	PB	RS		0-0	23-31-03	SM00793		S		SM00813		S		YC051-YL999, YR301-YR328
2601B	22	PB	SA		9-1	23-31-03	D11660	14			SM00814		S		YC051-YL999, YR301-YR328
2601R	22	PB	SA		0-0	23-31-03	D11660	13			SM00813		S		YC051-YL999, YR301-YR328
2611B	22	PB	SK		8-0	23-31-03	D11662	14			SM00814		S		YC051-YL999, YR301-YR328
2611R	22	PB	SK		0-0	23-31-03	D11662	13			SM00813		S		YC051-YL999, YR301-YR328
2613B	22	PB	SM		4-1	23-31-03	SM00814		S		SM00834		S		YC051-YL999, YR301-YR328
2613R	22	PB	SM		0-0	23-31-03	SM00813		S		SM00833		S		YC051-YL999, YR301-YR328
2621B	22	PB	SV		8-11	23-31-03	D11664	14			SM00834		S		YC051-YL999, YR301-YR328
2621B	22	PB	SV		7-3	23-31-03	D11664	14			SM00834		S		YN231-YN501
2621R	22	PB	SV		0-0	23-31-03	D11664	13			SM00833		S		ALL
2631B	22	PB	TF		8-0	23-31-03	D11666	14			SM00834		S		YC051-YL999, YR301-YR328
2631B	22	PB	TF		9-5	23-31-03	D11666	14			SM00834		S		YN231-YN501
2631R	22	PB	TF		0-0	23-31-03	D11666	13			SM00833		S		ALL
2633B	22	PB	TH		4-2	23-31-03	SM00834		S		SM00854		S		YC051-YL999, YR301-YR328
2633B	22	PB	TH		3-3	23-31-03	SM00834		S		SM00854		S		YN231-YN501
2633R	22	PB	TH		0-0	23-31-03	SM00833		S		SM00853		S		ALL

WIRE LIST

D280A108

91-21-11

Section W4250

Page 49

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)										
2641B	22	PB	TQ		8-9	23-31-03	D11668	14			SM00854		S		YC051-YL999, YR301-YR328
2641B	22	PB	TQ		10-2	23-31-03	D11668	14			SM00854		S		YN231-YN501
2641R	22	PB	TQ		0-0	23-31-03	D11668	13			SM00853		S		ALL
2651B	22	PB	UA		8-0	23-31-03	D11670	14			SM00854		S		YC051-YL999, YR301-YR328
2651B	22	PB	UA		11-0	23-31-03	D11670	14			SM00854		S		YN231-YN501
2651R	22	PB	UA		0-0	23-31-03	D11670	13			SM00853		S		ALL
2653B	22	PB	UC		4-0	23-31-03	SM00854		S		SM00874		S		YC051-YL999, YR301-YR328
2653B	22	PB	UC		8-1	23-31-03	SM00854		S		SM00874		S		YN231-YN501
2653R	22	PB	UC		0-0	23-31-03	SM00853		S		SM00873		S		ALL
2661B	22	PB	UK		8-8	23-31-03	D11672	14			SM00874		S		YC051-YL999, YR301-YR328
2661B	22	PB	UK		11-7	23-31-03	D11672	14			SM00874		S		YN231-YN501
2661R	22	PB	UK		0-0	23-31-03	D11672	13			SM00873		S		ALL
2671B	22	PB	UV		7-9	23-31-03	D11674	14			SM00874		S		YC051-YL999, YR301-YR328
2671R	22	PB	UV		0-0	23-31-03	D11674	13			SM00873		S		YC051-YL999, YR301-YR328
2673B	22	PB	UM		3-10	23-31-03	SM00874		S		SM00894		S		YC051-YL999, YR301-YR328
2673R	22	PB	UM		0-0	23-31-03	SM00873		S		SM00893		S		YC051-YL999, YR301-YR328
2681B	22	PB	VF		8-6	23-31-03	D11676	14			SM00894		S		YC051-YL999, YR301-YR328
2681B	22	PB	VF		11-2	23-31-03	D11676	14			SM00874		S		YN231-YN501
2681R	22	PB	VF		0-0	23-31-03	D11676	13			SM00873		S		YC051-YL999, YR301-YR328
2691B	22	PB	VQ		7-6	23-31-03	D11678	14			SM00894		S		YC051-YL999, YR301-YR328
2691B	22	PB	VQ		11-7	23-31-03	D11678	14			SM00874		S		YN231-YN501
2691R	22	PB	VQ		0-0	23-31-03	D11678	13			SM00893		S		YC051-YL999, YR301-YR328
2691R	22	PB	VQ		0-0	23-31-03	D11678	13			SM00873		S		YN231-YN501
2692B	18	PB	VR		4-5	33-23-21	SM00508		S		D40204J	2			YC051-YL999
2692B	18	PB	VR		4-6	33-23-21	SM00508		S		D40204J	2			YN231-YN260
2692B	18	PB	VR		6-11	33-23-21	SM00508		S		D40205J	2			YN501

WIRE LIST

D280A108

91-21-11
Section W4250
Page 50
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250		286A4250			P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
2692B		18		PB	VR	7-2	33-23-21	SM00508		S		D40205J	2			YR301-YR328
2692R		18		PB	VR	0-0	33-23-21	D40204J	1			SM00506		S		YC051-YN260
2692R		18		PB	VR	0-0	33-23-21	D40205J	1			SM00506		S		YN501-YR328
2693B		18		PB	VS	11-5	33-23-21	SM00568		S		D40204J	12			YC051-YL999
2693B		18		PB	VS	9-9	33-23-21	SM00568		S		D40204J	12			YN231-YN260
2693B		18		PB	VS	11-8	33-23-21	SM00568		S		D40205J	12			YN501
2693B		18		PB	VS	13-4	33-23-21	SM00568		S		D40205J	12			YR301-YR328
2693R		18		PB	VS	0-0	33-23-21	D40204J	6			SM00566		S		YC051-YN260
2693R		18		PB	VS	0-0	33-23-21	D40205J	6			SM00566		S		YN501-YR328
2694B		18		PB	VT	22-3	33-23-21	SM00628		S		D40204J	3			YC051-YL999
2694B		18		PB	VT	21-3	33-23-21	SM00648		S		D40204J	3			YN231-YN260
2694B		18		PB	VT	23-3	33-23-21	SM00648		S		D40205J	3			YN501
2694B		18		PB	VT	24-1	33-23-21	SM00628		S		D40205J	3			YR301-YR328
2694R		18		PB	VT	0-0	33-23-21	D40204J	8			SM00626		S		YC051-YL999
2694R		18		PB	VT	0-0	33-23-21	D40204J	8			SM00646		S		YN231-YN260
2694R		18		PB	VT	0-0	33-23-21	D40205J	8			SM00646		S		YN501
2694R		18		PB	VT	0-0	33-23-21	D40205J	8			SM00626		S		YR301-YR328
2695B		18		PB	VU	32-11	33-23-21	SM00688		S		D40204J	14			YC051-YL999
2695B		18		PB	VU	26-6	33-23-21	SM00668		S		D40204J	14			YN231-YN260
2695B		18		PB	VU	28-6	33-23-21	SM00668		S		D40205J	14			YN501
2695B		18		PB	VU	34-10	33-23-21	SM00688		S		D40205J	14			YR301-YR328
2695R		18		PB	VU	0-0	33-23-21	D40204J	13			SM00686		S		YC051-YL999
2695R		18		PB	VU	0-0	33-23-21	D40204J	13			SM00666		S		YN231-YN260
2695R		18		PB	VU	0-0	33-23-21	D40205J	13			SM00666		S		YN501
2695R		18		PB	VU	0-0	33-23-21	D40205J	13			SM00686		S		YR301-YR328
2696B		18		PB	VV	6-4	33-23-22	SM00748		S		D40206J	2			YC051-YL999
2696B		18		PB	VV	7-0	33-23-22	SM00708		S		D40206J	2			YN231-YN260
2696B		18		PB	VV	6-6	33-23-22	SM00708		S		D40207J	2			YN501
2696B		18		PB	VV	5-5	33-23-22	SM00748		S		D40207J	2			YR301-YR328
2696R		18		PB	VV	0-0	33-23-22	D40206J	1			SM00746		S		YC051-YL999
2696R		18		PB	VV	0-0	33-23-22	D40206J	1			SM00706		S		YN231-YN260
2696R		18		PB	VV	0-0	33-23-22	D40207J	1			SM00706		S		YN501
2696R		18		PB	VV	0-0	33-23-22	D40207J	1			SM00746		S		YR301-YR328
2697B		18		PB	VW	16-11	33-23-22	SM00808		S		D40206J	12			YC051-YL999
2697B		18		PB	VW	17-0	33-23-22	SM00748		S		D40206J	12			YN231-YN260
2697B		18		PB	VW	16-6	33-23-22	SM00748		S		D40207J	12			YN501
2697B		18		PB	VW	16-6	33-23-22	SM00808		S		D40207J	12			YR301-YR328
2697R		18		PB	VW	0-0	33-23-22	D40206J	6			SM00806		S		YC051-YL999
2697R		18		PB	VW	0-0	33-23-22	D40206J	6			SM00746		S		YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W4250

Page 51

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250			P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
2697R	18	PB	VW		0-0	33-23-22	D40207J	6			SM00746		S		YN501
2697R	18	PB	VW		0-0	33-23-22	D40207J	6			SM00806		S		YR301-YR328
2698B	18	PB	VX		24-0	33-23-22	D40206J	3			SM00848		S		YC051-YL999
2698B	18	PB	VX		23-0	33-23-22	SM00848		S		D40206J	3			YN231-YN260
2698B	18	PB	VX		22-6	33-23-22	SM00848		S		D40207J	3			YN501
2698B	18	PB	VX		23-8	33-23-22	D40207J	3			SM00848		S		YR301-YR328
2698R	18	PB	VX		0-0	33-23-22	D40206J	8			SM00846		S		YC051-YN260
2698R	18	PB	VX		0-0	33-23-22	D40207J	8			SM00846		S		YN501-YR328
2699B	22	PB	VY		10-11	23-31-03	SP00135		S		SM00514		S		YC051-YL999, YR301-YR328
2699B	22	PB	VY		11-0	23-31-03	SP00135		S		SM00514		S		YN231-YN501
2699R	22	PB	VY		0-0	23-31-03	SP00133		S		SM00513		S		ALL
2700B	22	PB	VZ		4-9	23-31-03	D40272P	12			SM00954		S		YC051-YL999, YR301-YR328
2700B	22	PB	VZ		5-4	23-31-03	D40272P	12			SM00874		S		YN231-YN501
2700R	22	PB	VZ		0-0	23-31-03	D40272P	15			SM00953		S		YC051-YL999, YR301-YR328
2700R	22	PB	VZ		0-0	23-31-03	D40272P	15			SM00873		S		YN231-YN501
2701B	22	PB	V1		8-0	23-31-03	D11680	14			SM00914		S		YC051-YL999, YR301-YR328
2701R	22	PB	V1		0-0	23-31-03	D11680	13			SM00913		S		YC051-YL999, YR301-YR328
2703B	22	PB	V3		2-4	23-31-03	SM00894		S		SM00914		S		YC051-YL999, YR301-YR328
2703R	22	PB	V3		0-0	23-31-03	SM00893		S		SM00913		S		YC051-YL999, YR301-YR328
2711B	22	PB	U1		9-9	23-31-03	D11682	14			SM00914		S		YC051-YL999, YR301-YR328
2711R	22	PB	U1		0-0	23-31-03	D11682	13			SM00913		S		YC051-YL999, YR301-YR328
2721B	22	PB	W1		8-5	23-31-03	D11684	14			SM00934		S		YC051-YL999, YR301-YR328
2721R	22	PB	W1		0-0	23-31-03	D11684	13			SM00933		S		YC051-YL999, YR301-YR328
2723B	22	PB	W3		4-2	23-31-03	SM00914		S		SM00934		S		YC051-YL999, YR301-YR328
2723R	22	PB	W3		0-0	23-31-03	SM00913		S		SM00933		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 52

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250			P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
2731B	22		PB	X1	11-2	23-31-03	D11686	14			SM00934		S		YC051-YL999, YR301-YR328
2731R	22		PB	X1	0-0	23-31-03	D11686	13			SM00933		S		YC051-YL999, YR301-YR328
2741B	22		PB	Y1	9-8	23-31-03	D11688	14			SM00954		S		YC051-YL999, YR301-YR328
2741R	22		PB	Y1	0-0	23-31-03	D11688	13			SM00953		S		YC051-YL999, YR301-YR328
2743B	22		PB	Y3	4-3	23-31-03	SM00934		S		SM00954		S		YC051-YL999, YR301-YR328
2743R	22		PB	Y3	0-0	23-31-03	SM00933		S		SM00953		S		YC051-YL999, YR301-YR328
2751B	22		PB	Z1	10-9	23-31-03	D11690	14			SM00954		S		YC051-YL999, YR301-YR328
2751R	22		PB	Z1	0-0	23-31-03	D11690	13			SM00953		S		YC051-YL999, YR301-YR328
2801B	18		PB	V8	30-8	33-23-22	D40206J	7			SM00888		S		YC051-YL999
2801B	18		PB	V8	30-4	33-23-22	D40207J	7			SM00888		S		YR301-YR328
2801R	18		PB	V8	0-0	33-23-22	D40206J	9			SM00886		S		YC051-YL999
2801R	18		PB	V8	0-0	33-23-22	D40207J	9			SM00886		S		YR301-YR328
2802B	18		PB	W8	36-1	33-23-22	D40206J	14			SM00928		S		YC051-YL999
2802B	18		PB	W8	35-8	33-23-22	D40207J	14			SM00928		S		YR301-YR328
2802R	18		PB	W8	0-0	33-23-22	D40206J	13			SM00926		S		YC051-YL999
2802R	18		PB	W8	0-0	33-23-22	D40207J	13			SM00926		S		YR301-YR328
5501WY	18		PA		4-2	33-25-32	SM00901		S		SM00921		S		YC051-YL999, YR301-YR328
5502WV	22		PA		4-2	33-27-32	SM00902		S		SM00922		S		YC051-YL999, YR301-YR328
5503WG	22		PA		4-2	33-27-32	SM00903		S		SM00923		S		YC051-YL999, YR301-YR328
5504WO	22		PA		4-2	33-27-32	SM00904		S		SM00924		S		YC051-YL999, YR301-YR328
5505V	22		PA		4-2	33-27-32	SM00905		S		SM00925		S		YC051-YL999, YR301-YR328
5507W	20		PA		4-2	33-25-32	SM00907		S		SM00927		S		YC051-YL999, YR301-YR328
5509A	16		CQ		4-2	35-21-31	SM00909		S		SM00929		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 53

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250			P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
5510K	18		PA		4-2	33-27-32	SM00910		S		SM00930		S		YC051-YL999, YR301-YR328
5521WY	18		PA		4-3	33-25-32	SM00921		S		SM00941		S		YC051-YL999, YR301-YR328
5522WV	22		PA		4-3	33-27-32	SM00922		S		SM00942		S		YC051-YL999, YR301-YR328
5523WG	22		PA		4-3	33-27-32	SM00923		S		SM00943		S		YC051-YL999, YR301-YR328
5524WO	22		PA		4-3	33-27-32	SM00924		S		SM00944		S		YC051-YL999, YR301-YR328
5525V	22		PA		4-3	33-27-32	SM00925		S		SM00945		S		YC051-YL999, YR301-YR328
5526N	18		PA		4-3	33-23-22	SM00926		S		SM00946		S		YC051-YL999, YR301-YR328
5527W	20		PA		4-3	33-25-32	SM00927		S		SM00947		S		YC051-YL999, YR301-YR328
5528O	18		PA		4-3	33-23-22	SM00928		S		SM00948		S		YC051-YL999, YR301-YR328
5529A	16		CQ		4-3	35-21-31	SM00929		S		SM00949		S		YC051-YL999, YR301-YR328
5530K	18		PA		4-3	33-27-32	SM00930		S		SM00950		S		YC051-YL999, YR301-YR328
5601WY	18		PA		8-0	33-25-32	D11680		1		SM00901		S		YC051-YL999, YR301-YR328
5602WV	22		PA		8-0	33-27-32	D11680		2		SM00902		S		YC051-YL999, YR301-YR328
5603WG	22		PA		8-0	33-27-32	D11680		3		SM00903		S		YC051-YL999, YR301-YR328
5604WO	22		PA		8-0	33-27-32	D11680		4		SM00904		S		YC051-YL999, YR301-YR328
5605V	22		PA		8-0	33-27-32	D11680		5		SM00905		S		YC051-YL999, YR301-YR328
5606N	18		PA		8-0	33-23-22	D11680		6		SM00906		S		YC051-YL999, YR301-YR328
5607W	20		PA		8-0	33-25-32	D11680		7		SM00907		S		YC051-YL999, YR301-YR328
5608O	18		PA		8-0	33-23-22	D11680		8		SM00908		S		YC051-YL999, YR301-YR328

WIRE LIST
D280A108

91-21-11
Section W4250
Page 54
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250			P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
5609A	16		CQ		8-0	35-21-31	D11680		11		SM00909		S		YC051-YL999, YR301-YR328
5610K	18		PA		8-0	33-27-32	D11680		10		SM00910		S		YC051-YL999, YR301-YR328
5611WY	18		PA		9-9	33-25-32	D11682		1		SM00901		S		YC051-YL999, YR301-YR328
5612WV	22		PA		9-9	33-27-32	D11682		2		SM00902		S		YC051-YL999, YR301-YR328
5613WG	22		PA		9-9	33-27-32	D11682		3		SM00903		S		YC051-YL999, YR301-YR328
5614WO	22		PA		9-9	33-27-32	D11682		4		SM00904		S		YC051-YL999, YR301-YR328
5615V	22		PA		9-9	33-27-32	D11682		5		SM00905		S		YC051-YL999, YR301-YR328
5616N	18		PA		9-9	33-23-22	D11682		6		SM00906		S		YC051-YL999, YR301-YR328
5617W	20		PA		9-9	33-25-32	D11682		7		SM00907		S		YC051-YL999, YR301-YR328
5618O	18		PA		9-9	33-23-22	D11682		8		SM00908		S		YC051-YL999, YR301-YR328
5619A	16		CQ		9-9	35-21-31	D11682		11		SM00909		S		YC051-YL999, YR301-YR328
5620K	18		PA		9-9	33-27-32	D11682		10		SM00910		S		YC051-YL999, YR301-YR328
5621WY	18		PA		8-5	33-25-32	D11684		1		SM00921		S		YC051-YL999, YR301-YR328
5622WV	22		PA		8-5	33-27-32	D11684		2		SM00922		S		YC051-YL999, YR301-YR328
5623WG	22		PA		8-5	33-27-32	D11684		3		SM00923		S		YC051-YL999, YR301-YR328
5624WO	22		PA		8-5	33-27-32	D11684		4		SM00924		S		YC051-YL999, YR301-YR328
5625V	22		PA		8-5	33-27-32	D11684		5		SM00925		S		YC051-YL999, YR301-YR328
5626N	18		PA		8-5	33-23-22	D11684		6		SM00926		S		YC051-YL999, YR301-YR328
5627W	20		PA		8-5	33-25-32	D11684		7		SM00927		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 55

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4250	286A4250			P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
5628O	18		PA		8-5	33-23-22	D11684		8		SM00928		S		YC051-YL999, YR301-YR328
5629A	16		CQ		8-5	35-21-31	D11684		11		SM00929		S		YC051-YL999, YR301-YR328
5630K	18		PA		8-5	33-27-32	D11684		10		SM00930		S		YC051-YL999, YR301-YR328
5631WY	18		PA		11-2	33-25-32	D11686		1		SM00921		S		YC051-YL999, YR301-YR328
5632WV	22		PA		11-2	33-27-32	D11686		2		SM00922		S		YC051-YL999, YR301-YR328
5633WG	22		PA		11-2	33-27-32	D11686		3		SM00923		S		YC051-YL999, YR301-YR328
5634WO	22		PA		11-2	33-27-32	D11686		4		SM00924		S		YC051-YL999, YR301-YR328
5635V	22		PA		11-2	33-27-32	D11686		5		SM00925		S		YC051-YL999, YR301-YR328
5636N	18		PA		11-2	33-23-22	D11686		6		SM00926		S		YC051-YL999, YR301-YR328
5637W	20		PA		11-2	33-25-32	D11686		7		SM00927		S		YC051-YL999, YR301-YR328
5638O	18		PA		11-2	33-23-22	D11686		8		SM00928		S		YC051-YL999, YR301-YR328
5639A	16		CQ		11-2	35-21-31	D11686		11		SM00929		S		YC051-YL999, YR301-YR328
5640K	18		PA		11-2	33-27-32	D11686		10		SM00930		S		YC051-YL999, YR301-YR328
5641WY	18		PA		9-8	33-25-32	D11688		1		SM00941		S		YC051-YL999, YR301-YR328
5642WV	22		PA		9-8	33-27-32	D11688		2		SM00942		S		YC051-YL999, YR301-YR328
5643WG	22		PA		9-8	33-27-32	D11688		3		SM00943		S		YC051-YL999, YR301-YR328
5644WO	22		PA		9-8	33-27-32	D11688		4		SM00944		S		YC051-YL999, YR301-YR328
5645V	22		PA		9-8	33-27-32	D11688		5		SM00945		S		YC051-YL999, YR301-YR328
5646N	18		PA		9-8	33-23-22	D11688		6		SM00946		S		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 56

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W4250	286A4250				P18 AND AB0340B DISC TO RIGHT PSU'S (continued)											
5647W	20		PA		9-8	33-25-32	D11688		7			SM00947		S		YC051-YL999, YR301-YR328
5648O	18		PA		9-8	33-23-22	D11688		8			SM00948		S		YC051-YL999, YR301-YR328
5649A	16		CQ		9-8	35-21-31	D11688		11			SM00949		S		YC051-YL999, YR301-YR328
5650K	18		PA		9-8	33-27-32	D11688		10			SM00950		S		YC051-YL999, YR301-YR328
5651WY	18		PA		10-9	33-25-32	D11690		1			SM00941		S		YC051-YL999, YR301-YR328
5652WV	22		PA		10-9	33-27-32	D11690		2			SM00942		S		YC051-YL999, YR301-YR328
5653WG	22		PA		10-9	33-27-32	D11690		3			SM00943		S		YC051-YL999, YR301-YR328
5654WO	22		PA		10-9	33-27-32	D11690		4			SM00944		S		YC051-YL999, YR301-YR328
5655V	22		PA		10-9	33-27-32	D11690		5			SM00945		S		YC051-YL999, YR301-YR328
5656N	18		PA		10-9	33-23-22	D11690		6			SM00946		S		YC051-YL999, YR301-YR328
5657W	20		PA		10-9	33-25-32	D11690		7			SM00947		S		YC051-YL999, YR301-YR328
5658O	18		PA		10-9	33-23-22	D11690		8			SM00948		S		YC051-YL999, YR301-YR328
5659A	16		CQ		10-9	35-21-31	D11690		11			SM00949		S		YC051-YL999, YR301-YR328
5660K	18		PA		10-9	33-27-32	D11690		10			SM00950		S		YC051-YL999, YR301-YR328
W4256	286A4256				P92 TO FWD GALLEY POWER											
0011	10		HA		24-2	25-31-11	D11458		F			D00570		A		ALL
0012	10		HA		24-2	25-31-11	D11458		E			D00570		B		ALL
0013	10		HA		24-2	25-31-11	D11458		D			D00570		C		ALL
0014	10		HA		2-1	25-31-11	D00570		D			GD03960	AC..	GY		ALL
0022	08		HA		3-2	24-51-21	D11458		G			GD00600	AC..	F		ALL
0101	10		HA		20-4	25-31-11	D11458		A			D01218		A		YC051-YD170
0101	08		HA		20-4	25-31-11	D11458		A			D01218		A		YL951-YL999, YR301-YR328
0102	10		HA		20-4	25-31-11	D11458		B			D01218		B		YC051-YD170

WIRE LIST

D280A108

91-21-11

Section W4250

Page 57

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4256	286A4256				P92 TO FWD GALLEY POWER (continued)										
0102	08		HA		20-4	25-31-11	D11458		B		D01218		B		YL951-YL999, YR301-YR328
0103	10		HA		20-4	25-31-11	D11458		C		D01218		C		YC051-YD170
0103	08		HA		20-4	25-31-11	D11458		C		D01218		C		YL951-YL999, YR301-YR328
0104	10		HA		2-4	25-31-11	D01218		D		GD08008	AC..	GY		YC051-YD170
0104	08		HA		2-4	25-31-11	D01218		D		GD08008	AC..	P		YL951-YL999, YR301-YR328
W4258	286A4258				AB0340B DISCONNECT TO RIGHT AFT OVERHEAD										
0011	20		PA		4-5	33-21-12	SM00001		S		D40210P		1		YC051-YL999
0011	20		PA		4-11	33-21-12	SM00001		S		D40210P		1		YN231-YN260
0012	20		PA		4-5	33-21-12	SM00002		S		D40210P		2		YC051-YL999
0012	20		PA		4-11	33-21-12	SM00002		S		D40210P		2		YN231-YN260
0021	20		PA		34-1	33-21-12	SM00001		S		SM00021		S		YC051-YL999
0021	20		PA		58-0	33-21-12	SM00001		S		SM00021		S		YN231-YN260
0022	20		PA		34-1	33-21-12	SM00002		S		SM00022		S		YC051-YL999
0022	20		PA		58-0	33-21-12	SM00002		S		SM00022		S		YN231-YN260
0031	20		PA		3-3	33-21-12	SM00021		S		D40212P		1		YC051-YL999
0031	20		PA		29-10	33-21-12	SM00021		S		D40212P		1		YN231-YN260
0032	20		PA		3-3	33-21-12	SM00022		S		D40212P		2		YC051-YL999
0032	20		PA		29-10	33-21-12	SM00022		S		D40212P		2		YN231-YN260
0041	20		PA		39-11	33-21-12	SM00021		S		D40214P		1		YC051-YL999
0041	20		PA		0-7	33-21-12	SM00021		S		D40214P		1		YN231-YN260
0042	20		PA		39-11	33-21-12	SM00022		S		D40214P		2		YC051-YL999
0042	20		PA		0-7	33-21-12	SM00022		S		D40214P		2		YN231-YN260
0086	18		PA		9-10	33-25-31	SM00106		S		D40204P		16		YC051-YL999
0086	18		PA		12-6	33-25-31	SM00106		S		D40204P		16		YN231-YN260
0086	18		PA		14-2	33-25-31	D40205P	16			SM00106		S		YN501
0086	18		PA		11-5	33-25-31	D40205P	16			SM00106		S		YR301-YR328
0087	20		PA		35-4	33-25-32	SM00107		S		D40206P		15		YC051-YL999
0087	20		PA		7-0	33-25-32	SM00107		S		D40206P		15		YN231-YN260
0087	20		PA		38-5	33-25-32	D40084J	7			D40207P		15		YN501
0087	20		PA		48-4	33-25-32	D40084J	7			D40207P		15		YR301-YR328
0088	20		PA		9-10	33-25-31	SM00108		S		D40204P		7		YC051-YL999
0088	20		PA		12-6	33-25-31	SM00108		S		D40204P		7		YN231-YN260
0088	20		PA		14-2	33-25-31	D40205P	7			SM00108		S		YN501
0088	20		PA		11-5	33-25-31	D40205P	7			SM00108		S		YR301-YR328
0089	18		PA		35-4	33-25-32	SM00109		S		D40206P		16		YC051-YL999

WIRE LIST

D280A108

91-21-11

Section W4250

Page 58

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4258		286A4258			AB0340B DISCONNECT TO RIGHT AFT OVERHEAD (continued)											
0089		18		PA		7-0	33-25-32	SM00109		S		D40206P	16			YN231-YN260
0089		18		PA		38-5	33-25-32	D40084J	9			D40207P	16			YN501
0089		18		PA		48-4	33-25-32	D40084J	9			D40207P	16			YR301-YR328
0091		18		PA		99-2	25-29-11	D40202J	24			D00158	=P	XR		YC051-YL999, YR301-YR328
0091		18		PA		79-3	25-29-11	D40202J	24			D00158	=P	XR		YN231-YN501
0092		18		PA		4-10	25-29-11	D00158	=G	XR		GD08050	ST..	1		YC051-YL999, YR301-YR328
0092		18		PA		4-2	25-29-11	D00158	=G	XR		GD08050	ST..	1		YN231-YN501
0093		18		PA		4-10	25-29-11	D00158	=N	XR		GD08050	AC..	1		YC051-YL999, YR301-YR328
0093		18		PA		4-2	25-29-11	D00158	=N	XR		GD08050	AC..	1		YN231-YN501
0106		18		PA		14-10	33-25-31	D40084J	10			SM00106		S		YC051-YL999, YR301-YR328
0106		18		PA		17-6	33-25-31	D40084J	10			SM00106		S		YN231-YN501
0107		20		PA		14-10	33-25-32	D40084J	7			SM00107		S		YC051-YL999
0107		20		PA		41-9	33-25-32	D40084J	7			SM00107		S		YN231-YN260
0108		20		PA		14-10	33-25-31	D40084J	8			SM00108		S		YC051-YL999, YR301-YR328
0108		20		PA		17-6	33-25-31	D40084J	8			SM00108		S		YN231-YN501
0109		18		PA		14-10	33-25-32	D40084J	9			SM00109		S		YC051-YL999
0109		18		PA		41-9	33-25-32	D40084J	9			SM00109		S		YN231-YN260
0201		20		PA		10-0	33-21-12	D40202J	1			SM00001		S		YC051-YL999
0201		20		PA		6-1	33-21-12	D40202J	1			SM00001		S		YN231-YN260
0202		20		PA		10-0	33-21-12	D40202J	2			SM00002		S		YC051-YL999
0202		20		PA		6-1	33-21-12	D40202J	2			SM00002		S		YN231-YN260
0203		20		PA		82-5	SPARE	D40202J	3			D40214P	CAP	Y		YC051-YL999
0203		20		PA		63-1	SPARE	D40202J	3			D40214P	CAP	Y		YN231-YN260
0204		20		PA		82-5	SPARE	D40202J	4			D40214P	CAP	Y		YC051-YL999
0204		20		PA		63-1	SPARE	D40202J	4			D40214P	CAP	Y		YN231-YN260
0225		20		PA		10-5	SPARE	D40202J	25			D40210P	CAP	Y		YC051-YL999
0225		20		PA		10-6	SPARE	D40202J	25			D40210P	CAP	Y		YN231-YN260
0226		20		PA		10-5	SPARE	D40202J	26			D40210P	CAP	Y		YC051-YL999
0226		20		PA		10-6	SPARE	D40202J	26			D40210P	CAP	Y		YN231-YN260
0268		18		PA		8-8	33-21-12	D40202J	2			D07177P	=1	VG		YN501-YR328
0269		18		PA		10-11	33-21-12	D40202J	1			D07178P	=1	VG		YN501-YR328
0301		20		PA		5-4	33-25-61	SM00108		S		D40862P	1			YC051-YL999
0301		20		PA		0-7	33-25-61	SM00108		S		D40862P	1			YN231-YN260
0301		18		PA		0-7	33-25-61	D40862P	1			SM00108		S		YN501

WIRE LIST

D280A108

91-21-11

Section W4250

Page 59

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W4258	286A4258				AB0340B DISCONNECT TO RIGHT AFT OVERHEAD (continued)											
0301	18		PA		5-4	33-25-61		SM00108		S		D40862P	1			YR301-YR328
0302	18		PA		5-4	33-25-61		SM00106		S		D40862P	2			YC051-YL999, YR301-YR328
0302	18		PA		0-7	33-25-61		SM00106		S		D40862P	2			YN231-YN260
0302	18		PA		0-7	33-25-61		D40862P	2			SM00106		S		YN501
0303	18		PA		4-6	33-25-61		D40862P	3			GD03846	AC..	1		ALL
0401	20		PA		37-4	33-25-61		SM00107		S		D40864P	1			YC051-YL999
0401	20		PA		0-7	33-25-61		SM00107		S		D40864P	1			YN231-YN260
0402	18		PA		37-4	33-25-61		SM00109		S		D40864P	2			YC051-YL999
0402	18		PA		0-7	33-25-61		SM00109		S		D40864P	2			YN231-YN260
0403	18		PA		2-8	33-25-61		D40864P	3			GD03804	AC..	1		YC051-YL999
0403	18		PA		2-9	33-25-61		D40864P	3			GD03804	AC..	1		YN231-YN260
0407	18		PA		6-1	33-24-11		D40202J	4			SM00114		S		YN501
0407	18		PA		1-7	33-24-11		D40202J	4			SM00114		S		YR301-YR328
0408	18		PA		65-0	33-24-11		D07168P	=1	VG		SM00114		S		YN501
0408	18		PA		88-4	33-24-11		D07168P	=1	VG		SM00114		S		YR301-YR328
0409	18		PA		4-4	33-24-11		D07166P	=1	VG		SM00114		S		YN501
0409	18		PA		1-11	33-24-11		D07166P	=1	VG		SM00114		S		YR301-YR314
0409	18		PA		1-11	33-24-11		D07166P	=1	VR		SM00114		S		YR315-YR328
2405B	18		PB	OE	49-2	33-23-22		D40202J	6			D40206P	14			YC051-YL999
2405B	18		PB	OE	48-5	33-23-22		D40202J	6			D40207P	14			YR301-YR328
2405R	18		PB	OE	0-0	33-23-22		D40202J	5			D40206P	13			YC051-YL999
2405R	18		PB	OE	0-0	33-23-22		D40202J	5			D40207P	13			YR301-YR328
2407B	18		PB	OG	10-5	33-23-21		D40202J	17			D40204P	2			YC051-YL999
2407B	18		PB	OG	10-6	33-23-21		D40202J	17			D40204P	2			YN231-YN260
2407B	18		PB	OG	11-5	33-23-21		D40202J	17			D40205P	2			YN501
2407B	18		PB	OG	11-6	33-23-21		D40202J	17			D40205P	2			YR301-YR328
2407R	18		PB	OG	0-0	33-23-21		D40202J	7			D40204P	1			YC051-YN260
2407R	18		PB	OG	0-0	33-23-21		D40202J	7			D40205P	1			YN501-YR328
2408B	18		PB	OH	10-5	33-23-21		D40202J	18			D40204P	12			YC051-YL999
2408B	18		PB	OH	10-6	33-23-21		D40202J	18			D40204P	12			YN231-YN260
2408B	18		PB	OH	11-5	33-23-21		D40202J	18			D40205P	12			YN501
2408B	18		PB	OH	11-6	33-23-21		D40202J	18			D40205P	12			YR301-YR328
2408R	18		PB	OH	0-0	33-23-21		D40202J	8			D40204P	6			YC051-YN260
2408R	18		PB	OH	0-0	33-23-21		D40202J	8			D40205P	6			YN501-YR328
2409B	18		PB	OI	10-5	33-23-21		D40202J	19			D40204P	3			YC051-YL999
2409B	18		PB	OI	10-6	33-23-21		D40202J	19			D40204P	3			YN231-YN260
2409B	18		PB	OI	11-5	33-23-21		D40202J	19			D40205P	3			YN501
2409B	18		PB	OI	11-6	33-23-21		D40202J	19			D40205P	3			YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 60

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4258		286A4258			AB0340B DISCONNECT TO RIGHT AFT OVERHEAD (continued)											
2409R		18		PB	OI	0-0	33-23-21	D40202J		9		D40204P		8		YC051-YN260
2409R		18		PB	OI	0-0	33-23-21	D40202J		9		D40205P		8		YN501-YR328
2410B		18		PB	OJ	10-5	33-23-21	D40202J		20		D40204P		14		YC051-YL999
2410B		18		PB	OJ	10-6	33-23-21	D40202J		20		D40204P		14		YN231-YN260
2410B		18		PB	OJ	11-5	33-23-21	D40202J		20		D40205P		14		YN501
2410B		18		PB	OJ	11-6	33-23-21	D40202J		20		D40205P		14		YR301-YR328
2410R		18		PB	OJ	0-0	33-23-21	D40202J		10		D40204P		13		YC051-YN260
2410R		18		PB	OJ	0-0	33-23-21	D40202J		10		D40205P		13		YN501-YR328
2411B		18		PB	OK	49-2	33-23-22	D40202J		21		D40206P		2		YC051-YL999
2411B		18		PB	OK	39-4	33-23-22	D40202J		21		D40206P		2		YN231-YN260
2411B		18		PB	OK	38-6	33-23-22	D40202J		21		D40207P		2		YN501
2411B		18		PB	OK	48-5	33-23-22	D40202J		21		D40207P		2		YR301-YR328
2411R		18		PB	OK	0-0	33-23-22	D40202J		11		D40206P		1		YC051-YN260
2411R		18		PB	OK	0-0	33-23-22	D40202J		11		D40207P		1		YN501-YR328
2412B		18		PB	OL	49-2	33-23-22	D40202J		22		D40206P		12		YC051-YL999
2412B		18		PB	OL	39-4	33-23-22	D40202J		22		D40206P		12		YN231-YN260
2412B		18		PB	OL	38-6	33-23-22	D40202J		22		D40207P		12		YN501
2412B		18		PB	OL	48-5	33-23-22	D40202J		22		D40207P		12		YR301-YR328
2412R		18		PB	OL	0-0	33-23-22	D40202J		12		D40206P		6		YC051-YN260
2412R		18		PB	OL	0-0	33-23-22	D40202J		12		D40207P		6		YN501-YR328
2413B		18		PB	OM	49-2	33-23-22	D40202J		23		D40206P		3		YC051-YL999
2413B		18		PB	OM	39-4	33-23-22	D40202J		23		D40206P		3		YN231-YN260
2413B		18		PB	OM	38-6	33-23-22	D40202J		23		D40207P		3		YN501
2413B		18		PB	OM	48-5	33-23-22	D40202J		23		D40207P		3		YR301-YR328
2413R		18		PB	OM	0-0	33-23-22	D40202J		13		D40206P		8		YC051-YN260
2413R		18		PB	OM	0-0	33-23-22	D40202J		13		D40207P		8		YN501-YR328
2415B		18		PB	OP	49-2	33-23-22	D40202J		16		D40206P		7		YC051-YL999
2415B		18		PB	OP	48-5	33-23-22	D40202J		16		D40207P		7		YR301-YR328
2415R		18		PB	OP	0-0	33-23-22	D40202J		15		D40206P		9		YC051-YL999
2415R		18		PB	OP	0-0	33-23-22	D40202J		15		D40207P		9		YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W4250

Page 61 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4722	286A4722			P91 TO APU-APU POWER LEADS											
0001	02	HA			8-1	24-21-31	G00013	T1	R		SM00004		GX		YC051-YC067
0001	02	HA			7-8	24-21-31	G00013	T1	R		SM00004		GX		YC068-YR328
0002	02	HA			7-11	24-21-31	G00013	T2	R		SM00005		GX		YC051-YC067
0002	02	HA			7-7	24-21-31	G00013	T2	R		SM00005		GX		YC068-YR328
0003	02	HA			7-10	24-21-31	G00013	T3	R		SM00006		GX		ALL
0004	04	HA			3-6	24-21-31	GD02564	AC..	R		G00013	N	R		YC051-YC067
0004	04	HA			3-0	24-21-31	GD02564	AC..	R		G00013	N	R		YC068-YR328
0005	*1	QY			87-4	24-21-31	SM00003		GJ		SM00006		GX		YC051-YC067
0005	*1	QY			85-8	24-21-31	SM00003		GJ		SM00006		GX		YC068-YL999, YR301-YR328
0005	*1	QY			66-6	24-21-31	SM00003		GJ		SM00006		GX		YN231-YN501
0006	*1	QY			87-4	24-21-31	SM00002		GJ		SM00005		GX		YC051-YC067
0006	*1	QY			87-5	24-21-31	SM00002		GJ		SM00005		GX		YC068-YL999, YR301-YR328
0006	*1	QY			68-3	24-21-31	SM00002		GJ		SM00005		GX		YN231-YN501
0007	*1	QY			87-3	24-21-31	SM00001		GJ		SM00004		GX		YC051-YC067
0007	*1	QY			89-1	24-21-31	SM00001		GJ		SM00004		GX		YC068-YL999, YR301-YR328
0007	*1	QY			69-11	24-21-31	SM00001		GJ		SM00004		GX		YN231-YN501
0008	*1	HA			20-7	24-21-31	TB5002	A	R		SM00001		GJ		YC051-YC067
0008	*1	HA			19-4	24-21-31	TB5002	A	R		SM00001		GJ		YC068-YR328
0009	*1	HA			21-1	24-21-31	TB5002	B	R		SM00002		GJ		ALL
0010	*1	HA			21-8	24-21-31	TB5002	C	R		SM00003		GJ		YC051-YC067
0010	*1	HA			22-10	24-21-31	TB5002	C	R		SM00003		GJ		YC068-YR328
W4724	286A4724			APU FIREWALL TO DISC BRACKET AB1050R											
0021	18	PA			15-0	33-35-11	S00087	1	G7		D40854J	4	18		YC053-YD158, YL951-YL954, YN231-YN235
0021	20	PA			15-0	33-35-11	S00087	1	G7		D40854J	4			YL955-YL968, YN236, YN501-YR328
0022	18	PA			13-4	33-35-11	S00087	2	G7		SM00002	9			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0023	18	PA			8-0	33-35-11	L00015	=P	BK		SM00002	9			YC053-YC059

WIRE LIST
D280A108

91-21-11
Section W4720
Page 1
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY	Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice
W4724	286A4724	APU FIREWALL TO DISC BRACKET AB1050R (continued)			
0023	18 PA		8-0 33-35-11	L00016 =P BK	SM00002 9 YC060-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0024	18 PA		4-10 33-35-11	L00016 =P BK	SM00002 9 YC053-YC059
0024	18 PA		4-10 33-35-11	L00015 =P BK	SM00002 9 YC060-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0025	18 PA		8-4 33-35-11	L00015 =G G7	GD00048 AC.. 1 YC053-YC059
0025	18 PA		8-4 33-35-11	L00016 =G G7	GD00048 AC.. 1 YC060-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0026	18 PA		13-7 33-35-11	L00016 =G G7	GD00048 AC.. 1 YC053-YC059
0026	18 PA		13-7 33-35-11	L00015 =G G7	GD00048 AC.. 1 YC060-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0034	18 PA		2-8 33-35-11	D40060J 6	GD00046 AC.. 1 YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0036	18 PA		2-8 33-35-11	D40060J 7	GD00046 AC.. 1 YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0515	20 PA		3-1 49-52-31	GD01240 DC.. 1	D10434 1 YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0517	20 PA		3-1 49-52-31	GD01240 DC.. 1	D10434 4 YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0549	20 PA		2-9 49-62-12	D10436 42	GD01240 DC.. 1 YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309

WIRE LIST

D280A108

91-21-11

Section W4720

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To					
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W4724	286A4724			APU FIREWALL TO DISC BRACKET AB1050R (continued)												
0549	20		PA		3-1	49-62-12	D10436		42		GD01240	DC..	1		YR312-YR328	
0560	20		PA		3-1	49-94-21	D10434		12		GD01240	DC..	1		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
0563	20		PA		3-1	49-94-21	D10434		19		GD01240	DC..	1		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
0575	22		GK		3-1	49-62-12	D10434		26		GD01240	DC..	1		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
0587	22		GK		3-1	49-62-12	D10434		27		GD01240	ST..	1		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
0589	20		PA		3-1	49-94-21	D10434		13		GD01240	DC..	1		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
0590	22		GK		3-1	49-94-21	D10434		14		GD01240	ST..	1		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
1001	18		VF	AA	18-7	33-35-11	D44584P		1		D40854J	3	18		YC053-YC067	
1001	18		VF	AA	18-8	33-35-11	D44584P		1		D40854J	3	18		YC068-YD158, YL951-YL954, YN231-YN235	
1001	18		VF	AA	18-8	33-35-11	D44584P		1		D40854J	53	18		YL955-YL968	
1001	18		VF	AA	18-9	33-35-11	D44584P		1		D40854J	53	18		YN236, YN501-YR328	
1001Z				AA	0-0	33-35-11	D44584P		S/R		D40854J			AQ	YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
1002	18		VF	AB	24-5	33-35-11	D44584P		2		GD00098	AC..	1		YC053-YC067	
1002	18		VF	AB	24-6	33-35-11	D44584P		2		GD00098	AC..	1		YC068-YD158, YL951-YL968, YN231-YN235	

WIRE LIST
D280A108

91-21-11
Section W4720
Page 3
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description		From				To					
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4724	286A4724			APU FIREWALL TO DISC BRACKET AB1050R (continued)											
1002	18	VF	AB		24-7	33-35-11	D44584P	2			GD00098	AC..	1		YN236, YN501-YR328
1002Z			AB		0-0	33-35-11	D44584P	S/R			GD00098	ST..	1		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1003	20	VF	AC		18-7	33-44-12	D40854J	6			D44584P		3		YC053-YC067
1003	20	VF	AC		18-8	33-44-12	D40854J	6			D44584P		3		YC068-YD158, YL951-YL968, YN231-YN235
1003	20	VF	AC		16-0	33-44-12	D40854J	6			D44582P		1		YN236, YN501-YR328
1003Z			AC		0-0	33-44-12	D40854J				D44584P		S/R		YC053-YD158, YL951-YL968, YN231-YN235
1003Z			AD		0-0	33-44-12	D40854J			AQ	D44582P		S/R		YN236, YN501-YR328
1004	20	VF	AD		24-5	33-44-12	GD00098	AC..	1		D44584P		4		YC053-YC067
1004	20	VF	AD		24-6	33-44-12	GD00098	AC..	1		D44584P		4		YC068-YD158, YL951-YL968, YN231-YN235
1004	20	VF	AD		21-10	33-44-12	GD00098	AC..	1		D44582P		2		YN236, YN501-YR328
1004Z			AD		0-0	33-44-12	D44584P	S/R			GD00098		ST..	1	YC053-YD158, YL951-YL968, YN231-YN235
1004Z			AD		0-0	33-44-12	D44582P	S/R			GD00098		ST..	1	YN236, YN501-YR328
1005	18	VF	AE		19-3	33-35-11	D40060J	5			D40854J		5	18	YC053-YD158, YL951-YL954, YN231-YN235
1005	20	VF	AE		19-3	33-35-11	D40060J	5			D40854J		5		YL955-YL968, YN236, YN501-YR328
1005Z			AE		0-0	33-35-11	D40060J	S/R			D40854J			AQ	YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1016	20	VF	AQ		16-4	49-52-31	D40854J	10			D10434		3		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W4720

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4724	286A4724			APU FIREWALL TO DISC BRACKET AB1050R (continued)											
1016Z				AQ	0-0	49-52-31	D40854J			AQ	D10434		S/R		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1018	20	VF	AS		16-4	49-52-31	D40854J		9		D10434		5		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1018Z				AS	0-0	49-52-31	D40854J			AQ	D10434		S/R		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1026	20	VF	BA		16-4	49-62-51	D40854J		48		D10434		7		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1026Z				BA	0-0	49-62-51	D40854J			BA	D10434		S/R		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1027	20	VF	BB		16-4	49-62-51	D40854J		49		D10434		18		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1027Z				BB	0-0	49-62-51	D40854J			BA	D10434		S/R		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1029	20	VF	BD		16-4	49-94-21	D40854J		50		D10434		11		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1029Z				BD	0-0	49-94-21	D40854J			BA	D10434		S/R		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328

WIRE LIST
D280A108

91-21-11
Section W4720
Page 5
Nov 12/2012

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4724	286A4724			APU FIREWALL TO DISC BRACKET AB1050R (continued)										
1033	20	VF	BH	16-4	49-94-21	D10434	29			D40854J	54			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1033Z			BH	0-0	49-94-21	D10434	S/R			D40854J			BA	YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1035	20	VF	BJ	16-4	49-94-21	D40854J	51			D10434	22			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1035Z			BJ	0-0	49-94-21	D40854J			BA	D10434	S/R			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1036	20	VF	BK	16-4	49-94-21	D40854J	52			D10434	9			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1036Z			BK	0-0	49-94-21	D40854J			BA	D10434	S/R			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1101R	18	H9	BN	28-7	26-11-31	M01925	T/1	GW		D40060J	2			YC053-YC067
1101R	18	H9	BN	28-8	26-11-31	M01925	T/1	GW		D40060J	2			YC068-YD158, YL951-YL968, YN231-YN235
1101R	18	H9	BN	28-0	26-11-31	M01925	T/1	GW		D40060J	2			YN236, YN501-YR328
1101Z			BN	0-0	26-11-31	M01925	DED			D40060J	S/R			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1108R	18	H9	BV	18-4	26-11-31	D40854J	1	18		M01925	T/1	GW		YC053-YC067
1108R	18	H9	BV	18-5	26-11-31	D40854J	1	18		M01925	T/1	GW		YC068-YD158, YL951-YL968, YN231-YN235
1108R	18	H9	BV	17-10	26-11-31	D40854J	1	18		M01925	T/1	GW		YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W4720

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4724	286A4724				APU FIREWALL TO DISC BRACKET AB1050R (continued)										
1108Z				BV	0-0	26-11-31	D40854J	S/R			M01925	DED			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1110R	20	H9	BX		19-3	26-11-31	D40060J	9			D40854J	2			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1110Z				BX	0-0	26-11-31	D40060J	S/R			D40854J	S/R			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1111R	20	H9	BY		2-8	26-11-31	D40060J	10			GD00046	DC..	1		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1111Z				BY	0-0	26-11-31	D40060J	DED			GD00046	DED			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1112R	20	H9	BZ		2-8	26-11-31	D40060J	3			GD00046	DC..	1		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1112Z				BZ	0-0	26-11-31	D40060J	DED			GD00046	DED			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1208	20	VF	DH		14-11	49-62-12	D40854J	25			D10436	18			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1208	20	VF	DH		14-6	49-62-12	D40854J	25			D10436	18			YR312-YR328
1208Z				DH	0-0	49-62-12	D40854J			AQ	D10436	S/R			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328

WIRE LIST
D280A108

91-21-11
Section W4720
Page 7
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type
W4724	286A4724			APU FIREWALL TO DISC BRACKET AB1050R (continued)										
1209	20	VF	DI	14-11	49-62-12	D40854J	26			D10436	32		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309	
1209	20	VF	DI	14-6	49-62-12	D40854J	26			D10436	32		YR312-YR328	
1209Z			DI	0-0	49-62-12	D40854J			AQ	D10436	S/R		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309	
1210	20	VF	DJ	14-11	49-62-12	D40854J	34			D10436	27		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309	
1210	20	VF	DJ	14-6	49-62-12	D40854J	34			D10436	27		YR312-YR328	
1210Z			DJ	0-0	49-62-12	D40854J			BA	D10436	S/R		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309	
1218	20	VF	DS	16-4	49-62-12	D40854J	33			D10434	25		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309	
1218Z			DS	0-0	49-62-12	D40854J			BA	D10434	S/R		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309	
2204B	20	VG	KD	16-4	49-41-11	D40854J	7			D10434	16		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309	
2204R	20	VG	KD	0-0	49-41-11	D40854J	8			D10434	17		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309	
2204Z			KD	0-0	49-41-11	D40854J	S/R			D10434	S/R		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309	

WIRE LIST

D280A108

91-21-11

Section W4720

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY	Fam	Description FT-IN Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W4724	286A4724		APU FIREWALL TO DISC BRACKET AB1050R (continued)									
2205B	22	HF	KE	14-11	49-52-31	D40854J	11	D10436	21			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309
2205B	22	HF	KE	14-6	49-52-31	D40854J	11	D10436	21			YR312-YR328
2205R	22	HF	KE	0-0	49-52-31	D40854J	12	D10436	8			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
2205Z			KE	0-0	49-52-31	D40854J	S/R	D10436	S/R			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
2206B	22	HF	KF	14-11	49-52-31	D40854J	16	D10436	22			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309
2206B	22	HF	KF	14-6	49-52-31	D40854J	16	D10436	22			YR312-YR328
2206R	22	HF	KF	0-0	49-52-31	D40854J	17	D10436	9			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
2206Z			KF	0-0	49-52-31	D40854J	S/R	D10436	S/R			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
2207B	22	HF	KG	14-11	49-52-31	D40854J	18	D10436	5			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309
2207B	22	HF	KG	14-6	49-52-31	D40854J	18	D10436	5			YR312-YR328
2207R	22	HF	KG	0-0	49-52-31	D40854J	19	D10436	1			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
2207Z			KG	0-0	49-52-31	D40854J	S/R	D10436	S/R			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328

WIRE LIST
D280A108

91-21-11
Section W4720
Page 9
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Description		From			To			Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type
W4724	286A4724			APU FIREWALL TO DISC BRACKET AB1050R (continued)										
2208B	22		HF	KH	14-11	49-52-31	D40854J	24		D10436	15		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309	
2208B	22		HF	KH	14-6	49-52-31	D40854J	24		D10436	15		YR312-YR328	
2208R	22		HF	KH	0-0	49-52-31	D40854J	43		D10436	30		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
2208Z				KH	0-0	49-52-31	D40854J	S/R		D10436	S/R		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
2214B	22		HF	KN	14-11	49-62-12	D40854J	27		D10436	34		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309	
2214B	22		HF	KN	14-6	49-62-12	D40854J	27		D10436	34		YR312-YR328	
2214R	22		HF	KN	0-0	49-62-12	D40854J	28		D10436	33		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
2214Z				KN	0-0	49-62-12	D40854J	S/R		D10436	S/R		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
2215B	22		HF	KP	14-11	49-62-12	D40854J	15		D10436	19		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309	
2215B	22		HF	KP	14-6	49-62-12	D40854J	15		D10436	19		YR312-YR328	
2215R	22		HF	KP	0-0	49-62-12	D40854J	30		D10436	35		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
2215Z				KP	0-0	49-62-12	D40854J	S/R		D10436	S/R		YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328	

WIRE LIST

D280A108

91-21-11

Section W4720

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY	Fam	Description FT-IN Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W4724	286A4724		APU FIREWALL TO DISC BRACKET AB1050R (continued)									
2216B	22	HF	KQ	14-11	49-62-12	D40854J	31	D10436	20			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309
2216B	22	HF	KQ	14-6	49-62-12	D40854J	31	D10436	20			YR312-YR328
2216R	22	HF	KQ	0-0	49-62-12	D40854J	32	D10436	36			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
2216Z			KQ	0-0	49-62-12	D40854J	S/R	D10436	S/R			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
2217B	22	HF	KR	14-11	49-62-12	D40854J	35	D10436	24			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309
2217B	22	HF	KR	14-6	49-62-12	D40854J	35	D10436	24			YR312-YR328
2217R	22	HF	KR	0-0	49-62-12	D40854J	36	D10436	3			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
2217Z			KR	0-0	49-62-12	D40854J	S/R	D10436	S/R			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
2218B	22	HF	KS	14-11	49-62-12	D40854J	37	D10436	29			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309
2218B	22	HF	KS	14-6	49-62-12	D40854J	37	D10436	29			YR312-YR328
2218R	22	HF	KS	0-0	49-62-12	D40854J	38	D10436	28			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
2218Z			KS	0-0	49-62-12	D40854J	S/R	D10436	S/R			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W4720

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4724	286A4724				APU FIREWALL TO DISC BRACKET AB1050R (continued)										
2219B	22		HF	KT	14-11	49-62-12	D40854J	22			D10436	12			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309
2219B	22		HF	KT	14-6	49-62-12	D40854J	22			D10436	12			YR312-YR328
2219R	22		HF	KT	0-0	49-62-12	D40854J	40			D10436	26			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
2219Z				KT	0-0	49-62-12	D40854J	S/R			D10436	S/R			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
2223B	22		HF	KX	16-4	49-62-51	D40854J	44			D10434	31			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
2223R	22		HF	KX	0-0	49-62-51	D40854J	45			D10434	30			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
2223Z				KX	0-0	49-62-51	D40854J	S/R			D10434	S/R			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
2224B	22		HF	KY	16-4	49-62-51	D40854J	46			D10434	33			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
2224R	22		HF	KY	0-0	49-62-51	D40854J	47			D10434	32			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
2224Z				KY	0-0	49-62-51	D40854J	S/R			D10434	S/R			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W4720

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4724	286A4724			APU FIREWALL TO DISC BRACKET AB1050R (continued)											
3201B	22		HG	YA	14-11	49-52-31	D40854J	13			D10436	10			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309
3201B	22		HG	YA	14-6	49-52-31	D40854J	13			D10436	10			YR312-YR328
3201R	22		HG	YA	0-0	49-52-31	D40854J	14			D10436	2			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
3201Y	22		HG	YA	0-0	49-52-31	D40854J	29			D10436	23			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
3201Z				YA	0-0	49-52-31	D40854J	S/R			D10436	S/R			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
3202B	22		HG	YB	14-11	49-52-31	D40854J	20			D10436	16			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309
3202B	22		HG	YB	14-6	49-52-31	D40854J	20			D10436	16			YR312-YR328
3202R	22		HG	YB	0-0	49-52-31	D40854J	21			D10436	31			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
3202Y	22		HG	YB	0-0	49-52-31	D40854J	39			D10436	6			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
3202Z				YB	0-0	49-52-31	D40854J	S/R			D10436	S/R			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
3203B	22		HG	YC	14-11	49-62-12	D40854J	41			D10436	11			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR309
3203B	22		HG	YC	14-6	49-62-12	D40854J	41			D10436	11			YR312-YR328

WIRE LIST
D280A108

91-21-11
Section W4720
Page 13
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4724 286A4724 APU FIREWALL TO DISC BRACKET AB1050R (continued)																
3203R		22		HG	YC	0-0	49-62-12	D40854J	42			D10436	4			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
3203Y		22		HG	YC	0-0	49-62-12	D40854J	23			D10436	25			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
3203Z					YC	0-0	49-62-12	D40854J	S/R			D10436	S/R			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
FRAQ						0-0	49-62-12	D40854J			AQ	D40854J	S/R			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
FRBA						0-0	49-94-21	D40854J			BA	D40854J	S/R			YC053-YD158, YL951-YL968, YN231-YN236, YN501-YR328
W4726 286A4726 AB1050R TO APU FIREWALL																
0535		20		PA		3-4	49-62-11	D00922	3			GD00048	DC..	1		YC053-YR328
1001		20		VF	AA	12-1	49-62-11	D40790J	9			D01246	1			YC053-YR328
1001Z					AA	0-0	49-62-11	D40790J	S/R			GD04805	ST..	E	*1	YC053-YR328
1002		20		VF	AB	12-1	49-62-11	D40790J	21			D01246	2			YC053-YR328
1002Z					AB	0-0	49-62-11	D40790J	S/R			GD04805	ST..	E	*1	YC053-YR328
1003		20		VF	AC	12-1	49-62-11	D40790J	22			D01246	4			YC053-YR328
1003Z					AC	0-0	49-62-11	D40790J	S/R			GD04805	ST..	E	*1	YC053-YR328
1004		20		VF	AD	11-3	49-62-11	D40790J	34			D00922	1			YC053-YR328
1004Z					AD	0-0	49-62-11	D40790J	S/R			GD04807	ST..	E	*	YC053-YR328
1005		20		VF	AE	11-3	49-62-11	D40790J	40			D00922	2			YC053-YR328
1005Z					AE	0-0	49-62-11	D40790J	S/R			GD04807	ST..	E	*	YC053-YR328
1103R		20		H9	BQ	15-3	26-21-11	D40790J	43			D01176	2			YC053-YR328
1103Z					BQ	0-0	26-21-11	D40790J	S/R			GD04813	ST..	E		YC053-YR328
1104R		18		H9	BR	4-6	26-21-11	D01176	1			GD00098	DC..	1		YC053-YR328
1104Z					BR	0-0	26-21-11	D01176	DED			GD00098	ST..	1		YC053-YR328
1105R		20		H9	BS	14-8	26-21-11	D00594	4			D40790J	20			YC053-YR328
1105Z					BS	0-0	26-21-11	GD04813	ST..	E		D40790J	S/R			YC053-YR328

WIRE LIST

D280A108

91-21-11

Section W4720

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W4726	286A4726				AB1050R TO APU FIREWALL (continued)										
1106R	18		H9	BT	3-11	26-21-11	D00594		5		GD00098	ST..	1		YC053-YR328
1106Z				BT	0-0	26-21-11	D00594	DED			GD00098	DED			YC053-YR328
1107R	18		H9	BU	3-11	26-21-11	D00594		3		GD00098	DC..	1		YC053-YR328
1107Z				BU	0-0	26-21-11	D00594	DED			GD00098	ST..	1		YC053-YR328
2201B	22		M2	KA	19-1	49-41-11	D40790J		10		D11118		30		YC053-YR328
2201R	22		M2	KA	0-0	49-41-11	D40790J		23		D11118		15		YC053-YR328
2201ZI				KA	0-0	49-41-11	D40790J		24	18	D11118		14		YC053-YR328
2201ZO				KA	0-0	49-41-11	D40790J	S/R			D11118	S/R			YC053-YR328
2202B	22		M2	KB	19-1	49-41-11	D40790J		11		D11118		28		YC053-YR328
2202R	22		M2	KB	0-0	49-41-11	D40790J		25		D11118		29		YC053-YR328
2202ZI				KB	0-0	49-41-11	D40790J		26	18	D11118		13		YC053-YR328
2202ZO				KB	0-0	49-41-11	D40790J	S/R			D11118	S/R			YC053-YR328
2203B	22		M2	KC	19-1	49-41-11	D40790J		12		D11118		27		YC053-YR328
2203R	22		M2	KC	0-0	49-41-11	D40790J		13		D11118		12		YC053-YR328
2203ZI				KC	0-0	49-41-11	D40790J		27	18	D11118		26		YC053-YR328
2203ZO				KC	0-0	49-41-11	D40790J	S/R			D11118	S/R			YC053-YR328
2209B	22		HF	KI	16-7	49-52-31	D40790J		14		D10912		23		YC053-YR328
2209R	22		HF	KI	0-0	49-52-31	D40790J		15		D10912		9		YC053-YR328
2209Z				KI	0-0	49-52-31	D40790J	S/R			D10912	S/R			YC053-YR328
2210B	22		HF	KJ	16-7	49-52-31	D40790J		17		D10912		10		YC053-YR328
2210R	22		HF	KJ	0-0	49-52-31	D40790J		35		D10912		2		YC053-YR328
2210Z				KJ	0-0	49-52-31	D40790J	S/R			D10912	S/R			YC053-YR328
2211B	22		HF	KK	16-7	49-52-31	D40790J		36		D10912		21		YC053-YR328
2211R	22		HF	KK	0-0	49-52-31	D40790J		37		D10912		8		YC053-YR328
2211Z				KK	0-0	49-52-31	D40790J	S/R			D10912	S/R			YC053-YR328
2220B	22		HF	KU	16-7	49-62-12	D40790J		28		D10912		19		YC053-YR328
2220R	22		HF	KU	0-0	49-62-12	D40790J		29		D10912		18		YC053-YR328
2220Z				KU	0-0	49-62-12	D40790J	S/R			D10912	S/R			YC053-YR328
2221B	22		HF	KV	16-7	49-62-12	D40790J		30		D10912		12		YC053-YR328
2221R	22		HF	KV	0-0	49-62-12	D40790J		31		D10912		26		YC053-YR328
2221Z				KV	0-0	49-62-12	D40790J	S/R			D10912	S/R			YC053-YR328
2222B	22		HF	KW	16-7	49-62-12	D40790J		32		D10912		24		YC053-YR328
2222R	22		HF	KW	0-0	49-62-12	D40790J		33		D10912		11		YC053-YR328
2222Z				KW	0-0	49-62-12	D40790J	S/R			D10912	S/R			YC053-YR328
2227B	22		HF	LB	16-7	49-71-21	D40790J		38		D10912		14		YC053-YR328
2227R	22		HF	LB	0-0	49-71-21	D40790J		39		D10912		13		YC053-YR328
2227Z				LB	0-0	49-71-21	D40790J	S/R			D10912	S/R			YC053-YR328
2232B	22		HF	LG	16-7	49-94-21	D40790J		47		D10912		36		YC053-YR328
2232R	22		HF	LG	0-0	49-94-21	D40790J		48		D10912		34		YC053-YR328

WIRE LIST

D280A108

91-21-11

Section W4720

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice Effectivity

W4726					286A4726					AB1050R TO APU FIREWALL (continued)				
2232Z			LG	0-0	49-94-21	D40790J	S/R			D10912	S/R			YC053-YR328
2236B	16	VG	LK	18-11	24-21-31	D40876J	6			D11118	8			YC053-YR328
2236R	16	VG	LK	0-0	24-21-31	D40876J	5			D11118	6			YC053-YR328
2236Z			LK	0-0	24-21-31	D40876J	7			D11118	19			YC053-YR328
3204B	16	VH	YD	18-11	24-21-31	D40876J	1			D11118	10			YC053-YR328
3204R	16	VH	YD	0-0	24-21-31	D40876J	2			D11118	25			YC053-YR328
3204Y	16	VH	YD	0-0	24-21-31	D40876J	3			D11118	24			YC053-YR328
3204Z			YD	0-0	24-21-31	D40876J	4			D11118	11			YC053-YR328
4103B	20	U4	Q6	19-1	24-24-31	D11118	23			D40790J	7			YC053-YR328
4103G	20	U4	Q6	0-0	24-24-31	D11118	4			D40790J	19			YC053-YR328
4103R	20	U4	Q6	0-0	24-24-31	D11118	3			D40790J	8			YC053-YR328
4103Y	20	U4	Q6	0-0	24-24-31	D11118	22			D40790J	18			YC053-YR328
4103Z			Q6	0-0	24-24-31	D11118	S/R			D40790J	S/R			YC053-YR328
4502G	20	DU	B8	16-7	49-71-21	D40790J	41	TC		D10912	5	4B		YC053-YR328
4502W	20	DU	B8	0-0	49-71-21	D40790J	42	TD		D10912	1	4D		YC053-YR328
4502Z			B8	0-0	49-71-21	D40790J	S/R			D10912	S/R			YC053-YR328
4504G	20	DU	D8	16-7	49-71-21	D40790J	44	TC		D10912	16	4B		YC053-YR328
4504W	20	DU	D8	0-0	49-71-21	D40790J	45	TD		D10912	15	4D		YC053-YR328
4504Z			D8	0-0	49-71-21	D40790J	S/R			D10912	S/R			YC053-YR328
YAAA				0-0	24-21-31	D40876J	S/R			D11118	S/R			YC053-YR328

WIRE LIST

D280A108

91-21-11

Section W4720

Page 16 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I W5001	286A5001			TCAS BOTTOM ANTENNA (E1-1 SHELF)											
I 001CO				AA	0-0	34-45-21	D04617P		= C1		D02753		= C1		ALL
I 001CX			0F	AA	13-4	34-45-21	D04617P		= A1		D02753		= A1		ALL
I 002CO				AB	0-0	34-45-21	D04619P		= C1		D02755		= C1		ALL
I 002CX			0F	AB	13-4	34-45-21	D04619P		= A1		D02755		= A1		ALL
I 003CO				AC	0-0	34-45-21	D04621P		= C1		D02757		= C1		ALL
I 003CX			0F	AC	13-4	34-45-21	D04621P		= A1		D02757		= A1		ALL
I 004CO				AD	0-0	34-45-21	D04623P		= C1		D02759		= C1		ALL
I 004CX			0F	AD	13-4	34-45-21	D04623P		= A1		D02759		= A1		ALL
W5005	286A5005			E5-2 TO E4-1 SHIP BUNDLE											
0008	20		PA		24-2	23-32-21	D40153P		A10		D45367J		A15		YL951-YL967, YN231-YN235
0009	22		PA		24-2	23-32-21	D40153P		A09		D45367J		A09		YL951-YL967, YN231-YN235
0010	22		PA		24-2	23-32-21	D40153P		B09		D45367J		B09		YL951-YL967, YN231-YN235
2502B	22		X2	AB	24-2	34-61-15	D40153P		B02		D45367J		B02		YL951-YN260
2502R	22		X2	AB	0-0	34-61-15	D40153P		A02		D45367J		A02		YL951-YN260
2502Z				AB	0-0	34-61-15	D40153P		PERG 1F		D45367J		PERG 1F		YL951-YN260
2504B	22		X2	AD	24-2	34-21-14	D40153P		B04		D45367J		B04		YL951-YN260
2504R	22		X2	AD	0-0	34-21-14	D40153P		A04		D45367J		A04		YL951-YN260
2504Z				AD	0-0	34-21-14	D40153P		PERG 1F		D45367J		PERG 1F		YL951-YN260
2505B	22		X2	AE	24-2	34-21-13	D40153P		B05		D45367J		B05		YL951-YN260
2505R	22		X2	AE	0-0	34-21-13	D40153P		A05		D45367J		A05		YL951-YN260
2505Z				AE	0-0	34-21-13	D40153P		PERG 1F		D45367J		PERG 1F		YL951-YN260

WIRE LIST

D280A108

91-21-11

Section W5000

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I	W5028	286A5028			P91 TO P92 AC TIE BUS											
I	0001	02		CQ		6-6	24-23-31	TB5004	A	H		TB5008	A	H		ALL
I	0002	02		CQ		6-6	24-23-31	TB5004	B	H		TB5008	B	H		ALL
I	0003	02		CQ		6-5	24-23-31	TB5004	C	H		TB5008	C	H		ALL

For training purposes only!

WIRE LIST

D280A108

91-21-11

Section W5020

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

	Bundle No.	Part Number			Description		From			To						Effectivity
	Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
I	W5030	286A5030			P91 TO T10 ANDP92											
I	0501	12		PA		12-3	24-52-11	D11420		A		D11446	1			ALL
I	0502	12		PA		12-3	24-52-11	D11420		B		D11446	2			ALL
I	0503	12		PA		12-3	24-52-11	D11420		C		D11446	3			ALL
I	0504	10		CQ		5-7	24-53-11	D11420		D		T00010	LV1	E		ALL
I	0505	10		CQ		2-6	24-53-11	T00010		G	E	GD00008	AC..	F		ALL
I	5501	20		CQ		12-8	21-27-31	D11800		2		D03472	1			ALL
I	5502	20		CQ		12-8	21-27-31	D11800		3		D03472	2			ALL
I	5503	20		CQ		12-8	21-27-31	D11800		4		D03472	3			ALL
I	5504	20		PA		2-6	21-27-31	D03472		7		GD01008	ST..	1A		ALL
I	5505	22		GK		12-8	21-27-31	D11800		6		D03472	5			ALL
I	5506	20		CQ		13-3	21-27-31	D03472		6		SP02002		S		ALL
I	W5032	286A5032			MAIN WHEEL WELL TO E/E BAY VIA CROWN											
I	2010B	22		PB	GJ	94-3	27-53-21	D40162P		B07		D42104J	8			YC051-YC055
I	2010B	22		PB	GJ	93-11	27-53-21	D40162P		B07		D42104J	8			YC056-YD158
I	2010B	22		PB	GJ	89-6	27-53-21	D40162P		B07		D42104J	8			YD160-YL999
I	2010B	22		PB	GJ	79-7	27-53-21	D40162P		B07		D42104J	8			YN231-YN260
I	2010B	22		PB	GJ	80-2	27-53-21	D40162P		B07		D42104J	8			YN501
I	2010B	22		PB	GJ	90-0	27-53-21	D40162P		B07		D42104J	8			YR301-YR328
I	2010R	22		PB	GJ	0-0	27-53-21	D40162P		A07		D42104J	7			ALL
I	2206B	22		X2	KF	94-3	27-52-11	D40162P		B08		D42104J	2			YC051-YC055
I	2206B	22		X2	KF	93-11	27-52-11	D40162P		B08		D42104J	2			YC056-YD158
I	2206B	22		X2	KF	89-6	27-52-11	D40162P		B08		D42104J	2			YD160-YL999
I	2206B	22		X2	KF	79-7	27-52-11	D40162P		B08		D42104J	2			YN231-YN260
I	2206B	22		X2	KF	80-2	27-52-11	D40162P		B08		D42104J	2			YN501
I	2206B	22		X2	KF	90-0	27-52-11	D40162P		B08		D42104J	2			YR301-YR328
I	2206R	22		X2	KF	0-0	27-52-11	D40162P		A08		D42104J	1			ALL
I	2206Z				KF	0-0	27-52-11	D40162P		A09		D42104J	3			ALL
I	2207B	20		X2	KG	94-3	27-52-11	D40162P		B10		D42104J	5			YC051-YC055
I	2207B	20		X2	KG	93-11	27-52-11	D40162P		B10		D42104J	5			YC056-YD158
I	2207B	20		X2	KG	89-6	27-52-11	D40162P		B10		D42104J	5			YD160-YL999
I	2207B	20		X2	KG	79-7	27-52-11	D40162P		B10		D42104J	5			YN231-YN260
I	2207B	20		X2	KG	80-2	27-52-11	D40162P		B10		D42104J	5			YN501
I	2207B	20		X2	KG	90-0	27-52-11	D40162P		B10		D42104J	5			YR301-YR328
I	2207R	20		X2	KG	0-0	27-52-11	D40162P		A10		D42104J	4			ALL
I	2207Z				KG	0-0	27-52-11	D40162P		B09		D42104J	6			ALL
I	3006B	22		PC	WF	94-3	27-53-21	D40162P		B02		D42104J	10			YC051-YC055
I	3006B	22		PC	WF	93-11	27-53-21	D40162P		B02		D42104J	10			YC056-YD158
I	3006B	22		PC	WF	89-6	27-53-21	D40162P		B02		D42104J	10			YD160-YL999

WIRE LIST

D280A108

91-21-11

Section W5030

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Diagram	From				To				Effectivity	
	Wire No.	GA	CO TY			Fam	FT-IN	Equip	Term	Type	Splice	Equip	Term		Type
W5032	286A5032			MAIN WHEEL WELL TO E/E BAY VIA CROWN (continued)											
3006B	22	PC	WF		79-7	27-53-21	D40162P	B02			D42104J	10			YN231-YN260
3006B	22	PC	WF		80-2	27-53-21	D40162P	B02			D42104J	10			YN501
3006B	22	PC	WF		90-0	27-53-21	D40162P	B02			D42104J	10			YR301-YR328
3006R	22	PC	WF		0-0	27-53-21	D40162P	B01			D42104J	9			ALL
3006Y	22	PC	WF		0-0	27-53-21	D40162P	B03			D42104J	11			ALL
3007B	22	PC	WG		94-3	27-53-21	D40162P	B05			D42104J	13			YC051-YC055
3007B	22	PC	WG		93-11	27-53-21	D40162P	B05			D42104J	13			YC056-YD158
3007B	22	PC	WG		89-6	27-53-21	D40162P	B05			D42104J	13			YD160-YL999
3007B	22	PC	WG		79-7	27-53-21	D40162P	B05			D42104J	13			YN231-YN260
3007B	22	PC	WG		80-2	27-53-21	D40162P	B05			D42104J	13			YN501
3007B	22	PC	WG		90-0	27-53-21	D40162P	B05			D42104J	13			YR301-YR328
3007R	22	PC	WG		0-0	27-53-21	D40162P	B04			D42104J	12			ALL
3007Y	22	PC	WG		0-0	27-53-21	D40162P	B06			D42104J	14			ALL
3008B	22	PC	WH		94-3	27-53-21	D40162P	A02			D42104J	17			YC051-YC055
3008B	22	PC	WH		93-11	27-53-21	D40162P	A02			D42104J	17			YC056-YD158
3008B	22	PC	WH		89-6	27-53-21	D40162P	A02			D42104J	17			YD160-YL999
3008B	22	PC	WH		79-7	27-53-21	D40162P	A02			D42104J	17			YN231-YN260
3008B	22	PC	WH		80-2	27-53-21	D40162P	A02			D42104J	17			YN501
3008B	22	PC	WH		90-0	27-53-21	D40162P	A02			D42104J	17			YR301-YR328
3008R	22	PC	WH		0-0	27-53-21	D40162P	A01			D42104J	16			ALL
3008Y	22	PC	WH		0-0	27-53-21	D40162P	A03			D42104J	18			ALL
3009B	22	PC	WI		94-3	27-53-21	D40162P	A05			D42104J	21			YC051-YC055
3009B	22	PC	WI		93-11	27-53-21	D40162P	A05			D42104J	21			YC056-YD158
3009B	22	PC	WI		89-6	27-53-21	D40162P	A05			D42104J	21			YD160-YL999
3009B	22	PC	WI		79-7	27-53-21	D40162P	A05			D42104J	21			YN231-YN260
3009B	22	PC	WI		80-2	27-53-21	D40162P	A05			D42104J	21			YN501
3009B	22	PC	WI		90-0	27-53-21	D40162P	A05			D42104J	21			YR301-YR328
3009R	22	PC	WI		0-0	27-53-21	D40162P	A04			D42104J	20			ALL
3009Y	22	PC	WI		0-0	27-53-21	D40162P	A06			D42104J	22			ALL
6001	20	CQ			3-0	28-21-11	SP00358		S		D42104J	25			ALL
W5036	286A5036			P91/P92 TO TRU'S 1,2 & 3.											
0501	08	CQ			13-10	24-32-11	D11426	A			D11736	C			ALL
0502	08	CQ			4-10	24-32-11	D11426	C			TB5210	1	E		ALL
0505	08	CQ			2-7	24-32-11	D11736	B			M01220	=C	P		ALL
0506	08	CQ			2-9	24-32-11	D11736	A			TB5420	2	P		ALL
W5039	286A5039			E1-2 TO S943 (D2709) COAX											
001CO			AA		0-0	34-53-31	D04607J	=C1			D02709	=C1			ALL

WIRE LIST

D280A108

91-21-11

Section W5030

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5039		286A5039			E1-2 TO S943 (D2709) COAX (continued)											
001CX			0G		AA	8-0	34-53-31	D04607J	= A1			D02709	= A1			ALL

For training purposes only!

WIRE LIST

D280A108

91-21-11

Section W5030

Page 3 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

	Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I	W5043	286A5043			IFE - (BSI) SERVER BASED SYSTEM ARINC INTERFACES (E5-2 TO E8-1)											
I	2501B	22		X2	AA	11-7	44-21-20	D45907P		12		D45319J	B06			YN501-YR328
I	2501R	22		X2	AA	0-0	44-21-20	D45907P		11		D45319J	A06			YN501-YR328
I	2501Z				AA	0-0	44-21-20	D45907P		S/R		D45319J	PERG	1F		YN501-YR328
I	2502B	22		X2	AB	11-7	44-21-20	D45907P		16		D45319J	B08			YN501-YR328
I	2502R	22		X2	AB	0-0	44-21-20	D45907P		15		D45319J	A08			YN501-YR328
I	2502Z				AB	0-0	44-21-20	D45907P		S/R		D45319J	PERG	1F		YN501-YR328
I	2503B	22		X2	AC	11-7	44-21-20	D45907P		4		D45319J	B02			YN501-YR328
I	2503R	22		X2	AC	0-0	44-21-20	D45907P		3		D45319J	A02			YN501-YR328
I	2503Z				AC	0-0	44-21-20	D45907P		S/R		D45319J	PERG	1F		YN501-YR328
I	2504B	22		X2	AD	11-7	44-21-20	D45907P		8		D45319J	B04			YN501-YR328
I	2504R	22		X2	AD	0-0	44-21-20	D45907P		7		D45319J	A04			YN501-YR328
I	2504Z				AD	0-0	44-21-20	D45907P		S/R		D45319J	PERG	1F		YN501-YR328
I	2505B	22		X2	AE	11-7	44-21-20	D45907P		10		D45319J	B03			YN501-YR328
I	2505R	22		X2	AE	0-0	44-21-20	D45907P		9		D45319J	A03			YN501-YR328
I	2505Z				AE	0-0	44-21-20	D45907P		S/R		D45319J	PERG	1F		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W5040

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I W5054	286A5054			CARGO COMPT SMOKE DETECTOR JUMPER BUNDLE											
I 0001	22		PA		1-1	26-16-22	D13846			4	D13844			4	YD160-YR328
I 0002	22		PA		1-1	26-16-22	D13846			12	D13844			12	YD160-YR328
I 0003	22		PA		1-1	26-16-22	D13846			5	D13844			5	YD160-YR328
I 0004	22		PA		1-1	26-16-22	D13846			11	D13844			11	YD160-YR328
I 0005	20		PA		1-1	26-16-22	D13846			10	D13844			10	YD160-YR328

WIRE LIST

D280A108

91-21-11

Section W5050

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5074	286A5074				CARGO FIRE EXTINGUISHER BOTTLE 2 (M2263) TO AB500DL (POS 6)										
6001	20		PA		2-2	26-23-11	D12816				GD05062	ST..	E		YC053-YC057
6001	20		PA		3-1	SPARE	D12816				GD05062	ST..	E		YC058-YD157, YL951-YR314, YR317-YR318, YR320-YR328 YD158-YD170, YR319
6001	20		PA		3-1	26-23-11	D12816				GD05062	ST..	E		YR315-YR316, YR319
6002	20		PA		2-2	26-23-11	D12816				GD05060	DC..	E		YC053-YC057
6002	20		PA		3-2	SPARE	D12816				GD05060	DC..	E		YC058-YD157, YL951-YR314, YR317-YR318, YR320-YR328 YD158-YD170, YR319
6002	20		PA		3-2	26-23-11	D12816				GD05060	DC..	E		YR315-YR316, YR319
6003	22		PA		12-7	26-23-11	D12816				D46608P	1			YC053-YC057
6003	22		PA		11-8	SPARE	D12816				D46608P	1			YC058-YD157, YL951-YR314, YR317-YR318, YR320-YR328 YD158-YD170, YR319
6003	22		PA		11-8	26-23-11	D12816				D46608P	1			YR315-YR316, YR319
6004	20		CQ		1-8	26-23-11	D12818				GD05066	DC..	E		YC053-YC057
6004	20		CQ		2-10	SPARE	D12818				GD05066	DC..	E		YC058-YD157, YL951-YR314, YR317-YR318, YR320-YR328 YD158-YD170, YR319
6004	20		CQ		2-10	26-23-11	D12818				GD05066	DC..	E		YR315-YR316, YR319
6005	20		CQ		1-10	26-23-11	D12818				GD05064	ST..	E		YC053-YC057
6005	20		CQ		2-10	SPARE	D12818				GD05064	ST..	E		YC058-YD157, YL951-YR314, YR317-YR318, YR320-YR328 YD158-YD170, YR319
6005	20		CQ		2-10	26-23-11	D12818				GD05064	ST..	E		YR315-YR316, YR319
6006	22		CQ		14-0	26-23-11	D12818				D46608P	12			YC053-YC057

WIRE LIST

D280A108

91-21-11

Section W5070

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To					
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W5074	286A5074				CARGO FIRE EXTINGUISHER BOTTLE 2 (M2263) TO AB500DL (POS 6) (continued)											
6006	22		CQ		14-3	SPARE	D12818		1		D46608P		12		YC058-YD157, YL951-YR314, YR317-YR318, YR320-YR328	
6006	22		CQ		14-3	26-23-11	D12818		1		D46608P		12		YD158-YD170, YR315-YR316, YR319	
6007	20		CQ		1-2	26-23-11	D12820		2		GD05066	DC..	E		YC053-YC057	
6007	20		CQ		1-9	SPARE	D12820		2		GD05066	DC..	E		YC058-YD157, YL951-YR314, YR317-YR318, YR320-YR328	
6007	20		CQ		1-9	26-23-11	D12820		2		GD05066	DC..	E		YD158-YD170, YR315-YR316, YR319	
6008	20		CQ		1-4	26-23-11	D12820		3		GD05064	ST..	E		YC053-YC057	
6008	20		CQ		1-9	SPARE	D12820		3		GD05064	ST..	E		YC058-YD157, YL951-YR314, YR317-YR318, YR320-YR328	
6008	20		CQ		1-9	26-23-11	D12820		3		GD05064	ST..	E		YD158-YD170, YR315-YR316, YR319	
6009	22		CQ		13-6	26-23-11	D12820		1		D46608P		9		YC053-YC057	
6009	22		CQ		13-2	SPARE	D12820		1		D46608P		9		YC058-YD157, YL951-YR314, YR317-YR318, YR320-YR328	
6009	22		CQ		13-2	26-23-11	D12820		1		D46608P		9		YD158-YD170, YR315-YR316, YR319	

WIRE LIST

D280A108

91-21-11

Section W5070

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5086	286A5086			FWD CARGO COMPT TO FWD CARGO SMOKE DETECTORS											
6001	22		PA		4-3	26-16-21	D12766		4		D12764		37		YC053-YC058
6001	22		PA		4-10	26-16-21	D12766		4		D12764		37		YC059-YR328
6002	22		PA		4-3	26-16-21	D12766		12		D12764		66		YC053-YC058
6002	22		PA		4-10	26-16-21	D12766		12		D12764		66		YC059-YR328
6003	22		PA		4-3	26-16-21	D12766		5		D12764		16		YC053-YC058
6003	22		PA		4-10	26-16-21	D12766		5		D12764		16		YC059-YR328
6004	22		PA		4-3	26-16-21	D12766		11		D12764		5		YC053-YC058
6004	22		PA		4-10	26-16-21	D12766		11		D12764		5		YC059-YR328
6005	20		PA		2-4	26-16-21	D12766		10		GD00430	ST..	1		YC053-YC058
6005	20		PA		2-10	26-16-21	D12766		10		GD00430	ST..	1		YC059-YD158
6005	20		PA		2-11	26-16-21	D12766		10		GD00430	ST..	1		YD160-YL999, YR301-YR328
6005	20		PA		2-9	26-16-21	D12766		10		GD00430	ST..	1		YN231-YN501
6006	22		PA		19-9	26-16-21	D12768		4		D12764		26		YC053-YC058
6006	22		PA		20-3	26-16-21	D12768		4		D12764		26		YC059-YD158
6006	22		PA		20-1	26-16-21	D12768		4		D12764		26		YD160-YL999, YR301-YR328
6006	22		PA		14-0	26-16-21	D12768		4		D12764		26		YN231-YN501
6007	22		PA		19-9	26-16-21	D12768		12		D12764		61		YC053-YC058
6007	22		PA		20-3	26-16-21	D12768		12		D12764		61		YC059-YD158
6007	22		PA		20-1	26-16-21	D12768		12		D12764		61		YD160-YL999, YR301-YR328
6007	22		PA		14-0	26-16-21	D12768		12		D12764		61		YN231-YN501
6008	22		PA		19-9	26-16-21	D12768		5		D12764		22		YC053-YC058
6008	22		PA		20-3	26-16-21	D12768		5		D12764		22		YC059-YD158
6008	22		PA		20-1	26-16-21	D12768		5		D12764		22		YD160-YL999, YR301-YR328
6008	22		PA		14-0	26-16-21	D12768		5		D12764		22		YN231-YN501
6009	22		PA		19-9	26-16-21	D12768		11		D12764		12		YC053-YC058
6009	22		PA		20-3	26-16-21	D12768		11		D12764		12		YC059-YD158
6009	22		PA		20-1	26-16-21	D12768		11		D12764		12		YD160-YL999, YR301-YR328
6009	22		PA		14-0	26-16-21	D12768		11		D12764		12		YN231-YN501
6010	20		PA		2-8	26-16-21	D12768		10		GD08048	ST..	1		YC053-YC058
6010	20		PA		3-2	26-16-21	D12768		10		GD08048	ST..	1		YC059-YD158
6010	20		PA		3-0	26-16-21	D12768		10		GD08048	ST..	1		YD160-YL999, YR301-YR328
6010	20		PA		3-10	26-16-21	D12768		10		GD01370	ST..	1		YN231-YN501
6011	22		CQ		12-9	26-16-21	D12770		4		D12764		13		YC053-YC058

WIRE LIST

D280A108

91-21-11

Section W5080

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W5086	286A5086				FWD CARGO COMPT TO FWD CARGO SMOKE DETECTORS (continued)												
6011	22		CQ		13-3	26-16-21		D12770		4		D12764		13		YC059-YD158	
6011	22		CQ		13-0	26-16-21		D12770		4		D12764		13		YD160-YL999, YR301-YR328	
6011	22		CQ		12-11	26-16-21		D12770		4		D12764		13		YN231-YN501	
6012	22		CQ		12-9	26-16-21		D12770		12		D12764		33		YC053-YC058	
6012	22		CQ		13-3	26-16-21		D12770		12		D12764		33		YC059-YD158	
6012	22		CQ		13-0	26-16-21		D12770		12		D12764		33		YD160-YL999, YR301-YR328	
6012	22		CQ		12-11	26-16-21		D12770		12		D12764		33		YN231-YN501	
6013	22		CQ		12-9	26-16-21		D12770		5		D12764		11		YC053-YC058	
6013	22		CQ		13-3	26-16-21		D12770		5		D12764		11		YC059-YD158	
6013	22		CQ		13-0	26-16-21		D12770		5		D12764		11		YD160-YL999, YR301-YR328	
6013	22		CQ		12-11	26-16-21		D12770		5		D12764		11		YN231-YN501	
6014	22		CQ		12-9	26-16-21		D12770		11		D12764		45		YC053-YC058	
6014	22		CQ		13-3	26-16-21		D12770		11		D12764		45		YC059-YD158	
6014	22		CQ		13-0	26-16-21		D12770		11		D12764		45		YD160-YL999, YR301-YR328	
6014	22		CQ		12-11	26-16-21		D12770		11		D12764		45		YN231-YN501	
6015	20		PA		3-8	26-16-21		D12770		10		GD00428	ST..	1		YC053-YC058	
6015	20		PA		4-2	26-16-21		D12770		10		GD00428	ST..	1		YC059-YD158	
6015	20		PA		3-10	26-16-21		D12770		10		GD00428	ST..	1		YD160-YL999, YR301-YR328	
6015	20		PA		3-9	26-16-21		D12770		10		GD00428	ST..	1		YN231-YN501	
6016	22		CQ		27-4	26-16-21		D12772		4		D12764		8		YC053-YC058	
6016	22		CQ		27-11	26-16-21		D12772		4		D12764		8		YC059-YD158	
6016	22		CQ		27-8	26-16-21		D12772		4		D12764		8		YD160-YL999, YR301-YR328	
6016	22		CQ		14-1	26-16-21		D12772		4		D12764		8		YN231-YN501	
6017	22		CQ		27-4	26-16-21		D12772		12		D12764		31		YC053-YC058	
6017	22		CQ		27-11	26-16-21		D12772		12		D12764		31		YC059-YD158	
6017	22		CQ		27-8	26-16-21		D12772		12		D12764		31		YD160-YL999, YR301-YR328	
6017	22		CQ		14-1	26-16-21		D12772		12		D12764		31		YN231-YN501	
6018	22		CQ		27-4	26-16-21		D12772		5		D12764		18		YC053-YC058	
6018	22		CQ		27-11	26-16-21		D12772		5		D12764		18		YC059-YD158	
6018	22		CQ		27-8	26-16-21		D12772		5		D12764		18		YD160-YL999, YR301-YR328	
6018	22		CQ		14-1	26-16-21		D12772		5		D12764		18		YN231-YN501	

WIRE LIST

D280A108

91-21-11

Section W5080

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W5086	286A5086				FWD CARGO COMPT TO FWD CARGO SMOKE DETECTORS (continued)											
6019	22		CQ		27-4	26-16-21		D12772	11			D12764	53			YC053-YC058
6019	22		CQ		27-11	26-16-21		D12772	11			D12764	53			YC059-YD158
6019	22		CQ		27-8	26-16-21		D12772	11			D12764	53			YD160-YL999, YR301-YR328
6019	22		CQ		14-1	26-16-21		D12772	11			D12764	53			YN231-YN501
6020	20		PA		5-3	26-16-21		D12772	10			GD08042	ST..	1		YC053-YC058
6020	20		PA		6-3	26-16-21		D12772	10			GD08042	ST..	1		YC059-YD158
6020	20		PA		6-0	26-16-21		D12772	10			GD08042	ST..	1		YD160-YL999, YR301-YR328
6020	20		PA		3-10	26-16-21		D12772	10			GD00086	ST..	1		YN231-YN501
6021	22		PA		0-7	26-16-21		D12764	65			D12764	20			YC053-YR328
6022	22		PA		0-7	26-16-21		D12764	60			D12764	14			YC053-YR328
6023	22		PA		0-7	26-16-21		D12764	54			D12764	29			YC053-YR328
6024	22		PA		0-7	26-16-21		D12764	47			D12764	46			YC053-YR328
6025	22		PA		0-7	26-16-21		D12764	35			D12764	48			YC053-YR328
6026	22		CQ		0-7	26-16-21		D12764	30			D12764	52			YC053-YR328
6027	22		CQ		0-7	26-16-21		D12764	50			D12764	64			YC053-YR328
6028	22		CQ		0-7	26-16-21		D12764	49			D12764	59			YC053-YR328
6029	22		CQ		0-7	26-16-21		D12764	58			D12764	36			YC053-YR328
6030	22		CQ		0-7	26-16-21		D12764	55			D12764	51			YC053-YR328
6031	22		PA		4-5	26-16-21		D12764	63			GD00430	ST..	1		YC053-YD158
6031	22		PA		4-9	26-16-21		D12764	63			GD00430	ST..	1		YD160-YL999, YR301-YR328
6031	22		PA		4-8	26-16-21		D12764	63			GD00430	ST..	1		YN231-YN501
W5088	286A5088				FWD CARGO COMPARTMENT TO E2-2 SHELF											
6001	22		CQ		13-6	26-16-21		D42014P	A06			D12762	5			YC053-YC055
6001	22		CQ		13-9	26-16-21		D42014P	A06			D12762	5			YC056-YR328
6002	22		PA		13-6	26-16-21		D42014P	A07			D12762	31			YC053-YC055
6002	22		PA		13-9	26-16-21		D42014P	A07			D12762	31			YC056-YR328
6003	22		CQ		13-6	26-16-21		D42014P	A08			D12762	23			YC053-YC055
6003	22		CQ		13-9	26-16-21		D42014P	A08			D12762	23			YC056-YR328
6004	22		PA		13-6	26-16-21		D42014P	A09			D12762	24			YC053-YC055
6004	22		PA		13-9	26-16-21		D42014P	A09			D12762	24			YC056-YR328
6005	22		CQ		13-6	26-16-21		D42014P	A10			D12762	26			YC053-YC055
6005	22		CQ		13-9	26-16-21		D42014P	A10			D12762	26			YC056-YR328
6006	22		CQ		13-6	26-16-21		D42014P	B05			D12762	28			YC053-YC055
6006	22		CQ		13-9	26-16-21		D42014P	B05			D12762	28			YC056-YR328
6007	22		CQ		13-6	26-16-21		D42014P	B06			D12762	6			YC053-YC055

WIRE LIST

D280A108

91-21-11

Section W5080

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W5088	286A5088				FWD CARGO COMPARTMENT TO E2-2 SHELF (continued)												
6007	22		CQ		13-9	26-16-21	D42014P		B06		D12762		6		YC056-YR328		
6008	22		CQ		13-6	26-16-21	D42014P		B07		D12762		9		YC053-YC055		
6008	22		CQ		13-9	26-16-21	D42014P		B07		D12762		9		YC056-YR328		
6009	22		PA		13-6	26-16-21	D42014P		B08		D12762		11		YC053-YC055		
6009	22		PA		13-9	26-16-21	D42014P		B08		D12762		11		YC056-YR328		
6010	22		PA		5-1	26-16-21	D12762		4		GD00430	DC..	1		YC053-YL999, YR301-YR328		
6010	22		PA		5-0	26-16-21	D12762		4		GD00430	DC..	1		YN231-YN501		
6011	22		PA		5-1	26-16-21	D12762		2		GD00430	DC..	1		YC053-YL999, YR301-YR328		
6011	22		PA		5-0	26-16-21	D12762		2		GD00430	DC..	1		YN231-YN501		
6012	22		PA		5-1	26-16-21	D12762		3		GD00430	ST..	1		YC053-YL999, YR301-YR328		
6012	22		PA		5-0	26-16-21	D12762		3		GD00430	ST..	1		YN231-YN501		
6013	22		CQ		0-7	26-16-21	D12762		20		D12762		34		YC053-YR328		
6014	22		PA		0-7	26-16-21	D12762		21		D12762		25		YC053-YR328		
6015	22		PA		30-5	SPARE	D46608J		1		D42014P	A05			YC053-YC055		
6015	22		PA		31-0	SPARE	D46608J		1		D42014P	A05			YC056-YD157, YL951-YL999, YR301-YR314, YR317-YR318, YR320-YR328		
6015	22		PA		31-0	26-23-11	D46608J		1		D42014P	A05			YD158-YD170, YR315-YR316, YR319		
6015	22		PA		20-11	SPARE	D46608J		1		D42014P	A05			YN231-YN501		
6016	22		CQ		30-5	SPARE	D46608J		12		D42014P	A01			YC053-YC055		
6016	22		CQ		31-0	SPARE	D46608J		12		D42014P	A01			YC056-YD157, YL951-YL999, YR301-YR314, YR317-YR318, YR320-YR328		
6016	22		CQ		31-0	26-23-11	D46608J		12		D42014P	A01			YD158-YD170, YR315-YR316, YR319		
6016	22		CQ		20-11	SPARE	D46608J		12		D42014P	A01			YN231-YN501		
6017	22		CQ		30-5	SPARE	D46608J		9		D42014P	A03			YC053-YC055		

WIRE LIST

D280A108

91-21-11

Section W5080

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Fam	Description FT-IN Diagram		From Equip Term Type Splice				To Equip Term Type Splice				Effectivity	
W5088	286A5088				FWD CARGO COMPARTMENT TO E2-2 SHELF (continued)											
6017	22		CQ		31-0	SPARE	D46608J		9			D42014P		A03		YC056-YD157, YL951-YL999, YR301-YR314, YR317-YR318, YR320-YR328
6017	22		CQ		31-0	26-23-11	D46608J		9			D42014P		A03		YD158-YD170, YR315-YR316, YR319
6017	22		CQ		20-11	SPARE	D46608J		9			D42014P		A03		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W5080

Page 5 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W5094	286A5094				AB500DL (POS 12) TO E2-2 SH4ELF										
6001	22		PA		30-7	26-16-22	D46606J				D41840P	A06			YC053-YC055
6001	22		PA		30-10	26-16-22	D46606J				D41840P	A06			YC056-YL999, YR301-YR328
6001	22		PA		21-0	26-16-22	D46606J				D41840P	A06			YN231-YN501
6002	22		CQ		30-7	26-16-22	D46606J				D41840P	A07			YC053-YC055
6002	22		CQ		30-10	26-16-22	D46606J				D41840P	A07			YC056-YL999, YR301-YR328
6002	22		CQ		21-0	26-16-22	D46606J				D41840P	A07			YN231-YN501
6003	22		PA		30-7	26-16-22	D46606J				D41840P	A08			YC053-YC055
6003	22		PA		30-10	26-16-22	D46606J				D41840P	A08			YC056-YL999, YR301-YR328
6003	22		PA		21-0	26-16-22	D46606J				D41840P	A08			YN231-YN501
6004	22		CQ		30-7	26-16-22	D46606J				D41840P	A09			YC053-YC055
6004	22		CQ		30-10	26-16-22	D46606J				D41840P	A09			YC056-YL999, YR301-YR328
6004	22		CQ		21-0	26-16-22	D46606J				D41840P	A09			YN231-YN501
6005	22		PA		30-7	26-16-22	D46606J				D41840P	A10			YC053-YC055
6005	22		PA		30-10	26-16-22	D46606J				D41840P	A10			YC056-YL999, YR301-YR328
6005	22		PA		21-0	26-16-22	D46606J				D41840P	A10			YN231-YN501
6006	22		PA		30-7	26-16-22	D46606J				D41840P	B05			YC053-YC055
6006	22		PA		30-10	26-16-22	D46606J				D41840P	B05			YC056-YL999, YR301-YR328
6006	22		PA		21-0	26-16-22	D46606J				D41840P	B05			YN231-YN501
6007	22		PA		30-7	26-16-22	D46606J				D41840P	B06			YC053-YC055
6007	22		PA		30-10	26-16-22	D46606J				D41840P	B06			YC056-YL999, YR301-YR328
6007	22		PA		21-0	26-16-22	D46606J				D41840P	B06			YN231-YN501
6008	22		PA		30-7	26-16-22	D46606J				D41840P	B07			YC053-YC055
6008	22		PA		30-10	26-16-22	D46606J				D41840P	B07			YC056-YL999, YR301-YR328
6008	22		PA		21-0	26-16-22	D46606J				D41840P	B07			YN231-YN501
6009	22		CQ		30-7	26-16-22	D46606J				D41840P	B08			YC053-YC055
6009	22		CQ		30-10	26-16-22	D46606J				D41840P	B08			YC056-YL999, YR301-YR328
6009	22		CQ		21-0	26-16-22	D46606J				D41840P	B08			YN231-YN501
6010	22		PA		30-7	26-23-11	D46606J				D41840P	A05			YC053-YC055
6010	22		PA		30-10	26-23-11	D46606J				D41840P	A05			YC056-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W5090

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W5094	286A5094				AB500DL (POS 12) TO E2-2 SH4ELF (continued)												
6010	22		PA		21-0	26-23-11	D46606J	24				D41840P	A05			YN231-YN501	
6011	22		CQ		30-7	26-23-11	D46606J	27				D41840P	A03			YC053-YC055	
6011	22		CQ		30-10	26-23-11	D46606J	27				D41840P	A03			YC056-YL999, YR301-YR328	
6011	22		CQ		21-0	26-23-11	D46606J	27				D41840P	A03			YN231-YN501	
6012	22		CQ		30-7	26-23-11	D46606J	30				D41840P	A01			YC053-YC055	
6012	22		CQ		30-10	26-23-11	D46606J	30				D41840P	A01			YC056-YL999, YR301-YR328	
6012	22		CQ		21-0	26-23-11	D46606J	30				D41840P	A01			YN231-YN501	
W5096	286A5096				AFT CARGO COMPART TO AFT CARGO SMOKE DETECTORS												
6001	22		PA		30-0	26-16-22	D12778	4				D12776	37			YC053-YC058	
6001	22		PA		30-6	26-16-22	D12778	4				D12776	37			YC059-YD158	
6001	22		PA		30-4	26-16-22	D12778	4				D12776	37			YD160-YL999, YR301-YR328	
6001	22		PA		20-6	26-16-22	D12778	4				D12776	37			YN231-YN501	
6002	22		PA		30-0	26-16-22	D12778	12				D12776	66			YC053-YC058	
6002	22		PA		30-6	26-16-22	D12778	12				D12776	66			YC059-YD158	
6002	22		PA		30-4	26-16-22	D12778	12				D12776	66			YD160-YL999, YR301-YR328	
6002	22		PA		20-6	26-16-22	D12778	12				D12776	66			YN231-YN501	
6003	22		PA		30-0	26-16-22	D12778	5				D12776	16			YC053-YC058	
6003	22		PA		30-6	26-16-22	D12778	5				D12776	16			YC059-YD158	
6003	22		PA		30-4	26-16-22	D12778	5				D12776	16			YD160-YL999, YR301-YR328	
6003	22		PA		20-6	26-16-22	D12778	5				D12776	16			YN231-YN501	
6004	22		PA		30-0	26-16-22	D12778	11				D12776	5			YC053-YC058	
6004	22		PA		30-6	26-16-22	D12778	11				D12776	5			YC059-YD158	
6004	22		PA		30-4	26-16-22	D12778	11				D12776	5			YD160-YL999, YR301-YR328	
6004	22		PA		20-6	26-16-22	D12778	11				D12776	5			YN231-YN501	
6005	20		PA		2-3	26-16-22	D12778	10				GD11732	ST..	1		YC053-YC058	
6005	20		PA		2-8	26-16-22	D12778	10				GD11732	ST..	1		YC059-YD158	
6005	20		PA		1-10	26-16-22	D12778	10				GD11732	ST..	1		YD160-YL999, YR301-YR328	
6005	20		PA		1-7	26-16-22	D12778	10				GD11732	ST..	1		YN231-YN501	
6006	22		PA		17-9	26-16-22	D12780	4				D12776	26			YC053-YC058	
6006	22		PA		18-3	26-16-22	D12780	4				D12776	26			YC059-YD158	

WIRE LIST

D280A108

91-21-11

Section W5090

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W5096	286A5096				AFT CARGO COMPART TO AFT CARGO SMOKE DETECTORS (continued)											
6006	22	PA		18-0	26-16-22	D12780		4		D12776	26			YD160-YL999, YR301-YR328		
6006	22	PA		14-0	26-16-22	D12780		4		D12776	26			YN231-YN501		
6007	22	PA		17-9	26-16-22	D12780		12		D12776	61			YC053-YC058		
6007	22	PA		18-3	26-16-22	D12780		12		D12776	61			YC059-YD158		
6007	22	PA		18-0	26-16-22	D12780		12		D12776	61			YD160-YL999, YR301-YR328		
6007	22	PA		14-0	26-16-22	D12780		12		D12776	61			YN231-YN501		
6008	22	PA		17-9	26-16-22	D12780		5		D12776	22			YC053-YC058		
6008	22	PA		18-3	26-16-22	D12780		5		D12776	22			YC059-YD158		
6008	22	PA		18-0	26-16-22	D12780		5		D12776	22			YD160-YL999, YR301-YR328		
6008	22	PA		14-0	26-16-22	D12780		5		D12776	22			YN231-YN501		
6009	22	PA		17-9	26-16-22	D12780		11		D12776	12			YC053-YC058		
6009	22	PA		18-3	26-16-22	D12780		11		D12776	12			YC059-YD158		
6009	22	PA		18-0	26-16-22	D12780		11		D12776	12			YD160-YL999, YR301-YR328		
6009	22	PA		14-0	26-16-22	D12780		11		D12776	12			YN231-YN501		
6010	20	PA		3-1	26-16-22	D12780		10		GD11004	ST..	1		YC053-YC058		
6010	20	PA		3-8	26-16-22	D12780		10		GD11004	ST..	1		YC059-YD158		
6010	20	PA		3-4	26-16-22	D12780		10		GD11004	ST..	1		YD160-YL999, YR301-YR328		
6010	20	PA		2-1	26-16-22	D12780		10		GD11774	ST..	1		YN231-YN501		
6011	22	PA		15-7	26-16-22	D12782		4		D12776	27			YC053-YC058		
6011	22	PA		16-0	26-16-22	D12782		4		D12776	27			YC059-YD158		
6011	22	PA		15-10	26-16-22	D12782		4		D12776	27			YD160-YL999, YR301-YR328		
6011	22	PA		15-6	26-16-22	D12782		4		D12776	27			YN231-YN501		
6012	22	PA		15-7	26-16-22	D12782		12		D12776	65			YC053-YC058		
6012	22	PA		16-0	26-16-22	D12782		12		D12776	65			YC059-YD158		
6012	22	PA		15-10	26-16-22	D12782		12		D12776	65			YD160-YL999, YR301-YR328		
6012	22	PA		15-6	26-16-22	D12782		12		D12776	65			YN231-YN501		
6013	22	PA		15-7	26-16-22	D12782		5		D12776	38			YC053-YC058		
6013	22	PA		16-0	26-16-22	D12782		5		D12776	38			YC059-YD158		
6013	22	PA		15-10	26-16-22	D12782		5		D12776	38			YD160-YL999, YR301-YR328		
6013	22	PA		15-6	26-16-22	D12782		5		D12776	38			YN231-YN501		
6014	22	PA		15-7	26-16-22	D12782		11		D12776	20			YC053-YC058		

WIRE LIST

D280A108

91-21-11

Section W5090

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type
W5096	286A5096				AFT CARGO COMPART TO AFT CARGO SMOKE DETECTORS (continued)										
6014	22		PA		16-0	26-16-22	D12782		11			D12776	20		YC059-YD158
6014	22		PA		15-10	26-16-22	D12782		11			D12776	20		YD160-YL999, YR301-YR328
6014	22		PA		15-6	26-16-22	D12782		11			D12776	20		YN231-YN501
6015	20		PA		6-8	26-16-22	D12782		10			GD11894	ST..	1	YC053-YC058, YN231-YN501
6015	20		PA		7-1	26-16-22	D12782		10			GD11894	ST..	1	YC059-YD158
6015	20		PA		6-11	26-16-22	D12782		10			GD11894	ST..	1	YD160-YL999, YR301-YR328
6016	22		CQ		33-3	26-16-22	D12784		4			D12776	13		YC053-YC058
6016	22		CQ		33-9	26-16-22	D12784		4			D12776	13		YC059-YD158
6016	22		CQ		33-7	26-16-22	D12784		4			D12776	13		YD160-YL999, YR301-YR328
6016	22		CQ		24-1	26-16-22	D12784		4			D12776	13		YN231-YN501
6017	22		CQ		33-3	26-16-22	D12784		12			D12776	33		YC053-YC058
6017	22		CQ		33-9	26-16-22	D12784		12			D12776	33		YC059-YD158
6017	22		CQ		33-7	26-16-22	D12784		12			D12776	33		YD160-YL999, YR301-YR328
6017	22		CQ		24-1	26-16-22	D12784		12			D12776	33		YN231-YN501
6018	22		CQ		33-3	26-16-22	D12784		5			D12776	11		YC053-YC058
6018	22		CQ		33-9	26-16-22	D12784		5			D12776	11		YC059-YD158
6018	22		CQ		33-7	26-16-22	D12784		5			D12776	11		YD160-YL999, YR301-YR328
6018	22		CQ		24-1	26-16-22	D12784		5			D12776	11		YN231-YN501
6019	22		CQ		33-3	26-16-22	D12784		11			D12776	45		YC053-YC058
6019	22		CQ		33-9	26-16-22	D12784		11			D12776	45		YC059-YD158
6019	22		CQ		33-7	26-16-22	D12784		11			D12776	45		YD160-YL999, YR301-YR328
6019	22		CQ		24-1	26-16-22	D12784		11			D12776	45		YN231-YN501
6020	20		PA		4-2	26-16-22	D12784		10			GD11730	ST..	1	YC053-YC058
6020	20		PA		4-8	26-16-22	D12784		10			GD11730	ST..	1	YC059-YD158
6020	20		PA		4-5	26-16-22	D12784		10			GD11730	ST..	1	YD160-YR328
6021	22		CQ		17-8	26-16-22	D12786		4			D12776	8		YC053-YC058
6021	22		CQ		18-1	26-16-22	D12786		4			D12776	8		YC059-YD158
6021	22		CQ		17-10	26-16-22	D12786		4			D12776	8		YD160-YL999, YR301-YR328
6021	22		CQ		15-11	26-16-22	D12786		4			D12776	8		YN231-YN501
6022	22		CQ		17-8	26-16-22	D12786		12			D12776	31		YC053-YC058
6022	22		CQ		18-1	26-16-22	D12786		12			D12776	31		YC059-YD158

WIRE LIST

D280A108

91-21-11

Section W5090

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W5096	286A5096				AFT CARGO COMPART TO AFT CARGO SMOKE DETECTORS (continued)											
6022	22		CQ		17-10	26-16-22		D12786		12			D12776	31		YD160-YL999, YR301-YR328
6022	22		CQ		15-11	26-16-22		D12786		12			D12776	31		YN231-YN501
6023	22		CQ		17-8	26-16-22		D12786		5			D12776	18		YC053-YC058
6023	22		CQ		18-1	26-16-22		D12786		5			D12776	18		YC059-YD158
6023	22		CQ		17-10	26-16-22		D12786		5			D12776	18		YD160-YL999, YR301-YR328
6023	22		CQ		15-11	26-16-22		D12786		5			D12776	18		YN231-YN501
6024	22		PA		17-8	26-16-22		D12786		11			D12776	53		YC053-YC058
6024	22		PA		18-1	26-16-22		D12786		11			D12776	53		YC059-YD158
6024	22		PA		17-10	26-16-22		D12786		11			D12776	53		YD160-YL999, YR301-YR328
6024	22		PA		15-11	26-16-22		D12786		11			D12776	53		YN231-YN501
6025	20		PA		2-5	26-16-22		D12786		10			GD11002	ST..	1	YC053-YC058
6025	20		PA		2-10	26-16-22		D12786		10			GD11002	ST..	1	YC059-YD158
6025	20		PA		2-8	26-16-22		D12786		10			GD11002	ST..	1	YD160-YL999, YR301-YR328
6025	20		PA		3-7	26-16-22		D12786		10			GD11738	ST..	1	YN231-YN501
6026	22		CQ		12-4	26-16-22		D12788		4			D12776	25		YC053-YC058
6026	22		CQ		12-10	26-16-22		D12788		4			D12776	25		YC059-YD158
6026	22		CQ		12-7	26-16-22		D12788		4			D12776	25		YD160-YL999, YR301-YR328
6026	22		CQ		12-2	26-16-22		D12788		4			D12776	25		YN231-YN501
6027	22		CQ		12-4	26-16-22		D12788		12			D12776	30		YC053-YC058
6027	22		CQ		12-10	26-16-22		D12788		12			D12776	30		YC059-YD158
6027	22		CQ		12-7	26-16-22		D12788		12			D12776	30		YD160-YL999, YR301-YR328
6027	22		CQ		12-2	26-16-22		D12788		12			D12776	30		YN231-YN501
6028	22		CQ		12-4	26-16-22		D12788		5			D12776	9		YC053-YC058
6028	22		CQ		12-10	26-16-22		D12788		5			D12776	9		YC059-YD158
6028	22		CQ		12-7	26-16-22		D12788		5			D12776	9		YD160-YL999, YR301-YR328
6028	22		CQ		12-2	26-16-22		D12788		5			D12776	9		YN231-YN501
6029	22		CQ		12-4	26-16-22		D12788		11			D12776	52		YC053-YC058
6029	22		CQ		12-10	26-16-22		D12788		11			D12776	52		YC059-YD158
6029	22		CQ		12-7	26-16-22		D12788		11			D12776	52		YD160-YL999, YR301-YR328
6029	22		CQ		12-2	26-16-22		D12788		11			D12776	52		YN231-YN501
6030	20		PA		2-4	26-16-22		D12788		10			GD11734	ST..	1	YC053-YC058

WIRE LIST

D280A108

91-21-11

Section W5090

Page 5

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W5096	286A5096				AFT CARGO COMPART TO AFT CARGO SMOKE DETECTORS (continued)											
6030	20	PA		2-10	26-16-22	D12788		10			GD11734	ST..	1	YC059-YD158		
6030	20	PA		2-7	26-16-22	D12788		10			GD11734	ST..	1	YD160-YL999, YR301-YR328		
6030	20	PA		2-5	26-16-22	D12788		10			GD11734	ST..	1	YN231-YN501		
6031	22	PA		0-7	26-16-22	D12776		60			D12776		14	YC053-YR328		
6032	22	PA		0-7	26-16-22	D12776		54			D12776		29	YC053-YR328		
6033	22	PA		0-7	26-16-22	D12776		47			D12776		46	YC053-YR328		
6034	22	PA		0-7	26-16-22	D12776		35			D12776		48	YC053-YR328		
6035	22	CQ		0-7	26-16-22	D12776		50			D12776		64	YC053-YR328		
6036	22	CQ		0-7	26-16-22	D12776		49			D12776		59	YC053-YR328		
6037	22	CQ		0-7	26-16-22	D12776		58			D12776		36	YC053-YR328		
6038	22	CQ		0-7	26-16-22	D12776		55			D12776		51	YC053-YR328		
6039	22	PA		1-11	26-16-22	D12776		63			GD11830	ST..	1	YC053-YR328		
W5098	286A5098				AFT CARGO COMPT TO E2-2 SHELF											
6001	22	PA		58-0	26-16-22	D12774		5			D46606P		1	YC053-YD157		
6001	22	PA		58-2	26-16-22	D12774		5			D46606P		1	YD158-YL999, YR301-YR328		
6001	22	PA		48-4	26-16-22	D12774		5			D46606P		1	YN231-YN501		
6002	22	CQ		58-0	26-16-22	D12774		31			D46606P		2	YC053-YD157		
6002	22	CQ		58-2	26-16-22	D12774		31			D46606P		2	YD158-YL999, YR301-YR328		
6002	22	CQ		48-4	26-16-22	D12774		31			D46606P		2	YN231-YN501		
6003	22	PA		58-0	26-16-22	D12774		23			D46606P		3	YC053-YD157		
6003	22	PA		58-2	26-16-22	D12774		23			D46606P		3	YD158-YL999, YR301-YR328		
6003	22	PA		48-4	26-16-22	D12774		23			D46606P		3	YN231-YN501		
6004	22	CQ		58-0	26-16-22	D12774		24			D46606P		4	YC053-YD157		
6004	22	CQ		58-2	26-16-22	D12774		24			D46606P		4	YD158-YL999, YR301-YR328		
6004	22	CQ		48-4	26-16-22	D12774		24			D46606P		4	YN231-YN501		
6005	22	PA		58-0	26-16-22	D12774		26			D46606P		5	YC053-YD157		
6005	22	PA		58-2	26-16-22	D12774		26			D46606P		5	YD158-YL999, YR301-YR328		
6005	22	PA		48-4	26-16-22	D12774		26			D46606P		5	YN231-YN501		
6006	22	PA		58-0	26-16-22	D12774		28			D46606P		6	YC053-YD157		
6006	22	PA		58-2	26-16-22	D12774		28			D46606P		6	YD158-YL999, YR301-YR328		
6006	22	PA		48-4	26-16-22	D12774		28			D46606P		6	YN231-YN501		

WIRE LIST

D280A108

91-21-11

Section W5090

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5098	286A5098				AFT CARGO COMPT TO E2-2 SHELF (continued)										
6007	22		PA		58-0	26-16-22	D12774		6		D46606P		7		YC053-YD157
6007	22		PA		58-2	26-16-22	D12774		6		D46606P		7		YD158-YL999, YR301-YR328
6007	22		PA		48-4	26-16-22	D12774		6		D46606P		7		YN231-YN501
6008	22		PA		58-0	26-16-22	D12774		9		D46606P		8		YC053-YD157
6008	22		PA		58-2	26-16-22	D12774		9		D46606P		8		YD158-YL999, YR301-YR328
6008	22		PA		48-4	26-16-22	D12774		9		D46606P		8		YN231-YN501
6009	22		CQ		58-0	26-16-22	D12774		11		D46606P		9		YC053-YD157
6009	22		CQ		58-2	26-16-22	D12774		11		D46606P		9		YD158-YL999, YR301-YR328
6009	22		CQ		48-4	26-16-22	D12774		11		D46606P		9		YN231-YN501
6010	20		PA		2-11	26-23-11	D12792		1		GD04836	ST..	E		YC053-YC057
6010	20		PA		3-1	26-23-11	D12792		1		GD04836	ST..	E		YC058-YL999, YR301-YR328
6010	20		PA		2-8	26-23-11	D12792		1		GD04836	ST..	E		YN231-YN501
6011	20		PA		2-11	26-23-11	D12792		2		GD04834	DC..	E		YC053-YC057
6011	20		PA		3-1	26-23-11	D12792		2		GD04834	DC..	E		YC058-YD157
6011	20		PA		3-2	26-23-11	D12792		2		GD04834	DC..	E		YD158-YL999, YR301-YR328
6011	20		PA		2-8	26-23-11	D12792		2		GD04834	DC..	E		YN231-YN501
6012	22		PA		8-11	26-23-11	D12792		3		D46606P		24		YC053-YC057, YD158-YL999, YR301-YR328
6012	22		PA		9-1	26-23-11	D12792		3		D46606P		24		YC058-YD157
6012	22		PA		8-8	26-23-11	D12792		3		D46606P		24		YN231-YN501
6013	20		CQ		2-4	26-23-11	D12794		2		GD04840	DC..	E		YC053-YC057
6013	20		CQ		2-10	26-23-11	D12794		2		GD04840	DC..	E		YC058-YD157
6013	20		CQ		2-2	26-23-11	D12794		2		GD04840	DC..	E		YD158-YL999, YR301-YR328
6013	20		CQ		2-6	26-23-11	D12794		2		GD04840	DC..	E		YN231-YN501
6014	20		CQ		2-1	26-23-11	D12794		3		GD04838	ST..	E		YC053-YC057
6014	20		CQ		2-6	26-23-11	D12794		3		GD04838	ST..	E		YC058-YD157
6014	20		CQ		2-2	26-23-11	D12794		3		GD04838	ST..	E		YD158-YL999, YR301-YR328
6014	20		CQ		2-3	26-23-11	D12794		3		GD04838	ST..	E		YN231-YN501
6015	22		CQ		8-10	26-23-11	D12794		1		D46606P		27		YC053-YC057
6015	22		CQ		9-4	26-23-11	D12794		1		D46606P		27		YC058-YD157

WIRE LIST

D280A108

91-21-11

Section W5090

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5098		286A5098			AFT CARGO COMPT TO E2-2 SHELF (continued)											
6015		22		CQ		9-2	26-23-11	D12794		1		D46606P		27		YD158-YL999, YR301-YR328
6015		22		CQ		9-0	26-23-11	D12794		1		D46606P		27		YN231-YN501
6016		20		CQ		1-11	26-23-11	D12796		2		GD04840	DC..	E		YC053-YC057
6016		20		CQ		2-0	26-23-11	D12796		2		GD04840	DC..	E		YC058-YD157
6016		20		CQ		1-7	26-23-11	D12796		2		GD04840	DC..	E		YD158-YL999, YR301-YR328
6016		20		CQ		1-10	26-23-11	D12796		2		GD04840	DC..	E		YN231-YN501
6017		20		CQ		1-7	26-23-11	D12796		3		GD04838	ST..	E		YC053-YC057, YD158-YL999, YR301-YR328
6017		20		CQ		1-8	26-23-11	D12796		3		GD04838	ST..	E		YC058-YD157
6017		20		CQ		1-6	26-23-11	D12796		3		GD04838	ST..	E		YN231-YN501
6018		22		CQ		8-4	26-23-11	D12796		1		D46606P		30		YC053-YC057, YN231-YN501
6018		22		CQ		8-6	26-23-11	D12796		1		D46606P		30		YC058-YD157
6018		22		CQ		8-7	26-23-11	D12796		1		D46606P		30		YD158-YL999, YR301-YR328
6019		22		PA		1-11	26-16-22	D12774		4		GD11830	DC..	1		YC053-YR328
6020		22		PA		1-11	26-16-22	D12774		2		GD11830	DC..	1		YC053-YR328
6021		22		PA		1-11	26-16-22	D12774		3		GD11830	ST..	1		YC053-YR328
6022		22		PA		0-7	26-16-22	D12774		20		D12774		34		YC053-YR328
6023		22		CQ		0-7	26-16-22	D12774		21		D12774		25		YC053-YR328
W5099		286A5099			TCAS SUPPRESSION E1-5 TO M1908 (E1 RACK)											
001CO					AA	0-0	34-53-31	D41511J		= C1		D10159		= C1		ALL
001CX				OF	AA	9-10	34-53-31	D41511J		= A1		D10159		= A1		ALL

WIRE LIST

D280A108

91-21-11

Section W5090

Page 8 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W5100	286A5100				J24 TO J20 & J22: J-BOX INTERCONNECT BUNDLE											
0001	24		PK		14-6		34-49-11	D40668P		16		D40698P	26			YC053-YD158, YL951-YR328
0002	24		PK		14-6		34-49-11	D40668P		17		D40698P	25			YC053-YD158, YL951-YR328
0003	24		PK		14-6		99-99-99	D40698P		24		D40668P	10			YC053-YD158, YL951-YR328
0004	24		PK		14-6		34-49-11	D40668P		19		D40698P	30			YC053-YD158, YL953-YL999, YN235-YR328
0004	24		PK		14-6		MULTI	D40668P		19		D40698P	30			YL951-YL952, YN231-YN234
0005	24		PK		14-6		34-49-11	D40668P		18		D40698P	31			YC053-YD158, YL951-YR328
0006	22		PA		14-6		23-71-01	D40668P		31		D40698P	2			YC051-YD158, YL951-YR328
0007	22		PA		14-6		23-71-01	D40668P		6		D40698P	5			YC051-YD158, YL951-YR328
0012	22		PA		14-6		21-25-11	D40698P		32		D40668P	32			YC060-YC064
0012	22		PA		14-6		21-25-11	D40668P		32		D40698P	32			YL951-YR328
0013	22		PA		14-6		21-25-11	D40698P		33		D40668P	33			YC060-YC064
0013	22		PA		14-6		21-25-11	D40668P		33		D40698P	33			YL951-YR328
0014	24		PK		14-6		21-43-21	D40668P		34		D40698P	34			YL951-YR328
0015	24		PK		14-6		21-43-21	D40668P		42		D40698P	35			YL951-YR328
0021	22		PA		14-6		44-21-22	D40668P		35		D40698P	36			YN501-YR328
0502	22		PA		14-6		31-31-11	D40668P		3		D40698P	3			YC051-YD158, YL951-YR328
0503	22		PA		14-6		31-31-11	D40668P		4		D40698P	4			YC051-YD158, YL951-YR328
0506	22		PA		8-4		32-51-11	D02864		3		D40632P	6			YC051-YD158, YL951-YR328
0507	22		PA		3-10		32-51-11	D02864		1		GD00032	ST..	E		YC051-YD158, YL951-YR328
0508	22		PA		3-10		32-51-11	D02864		5		GD00030	AC..	E		YC051-YD158, YL951-YR328
0509	22		PA		8-4		32-51-11	D02864		4		D40632P	7			YC051-YD158, YL951-YR328
0510	24		PK		13-11		21-27-31	D40632P		8		D40698P	15			YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5100

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W5100	286A5100				J24 TO J20 & J22: J-BOX INTERCONNECT BUNDLE (continued)											
0511	22		CQ		8-0	27-62-11		D40668P				D40632P	11			YC051-YD158, YL951-YR328
0512	22		CQ		8-0	27-62-11		D40668P				D40632P	12			YC051-YD158, YL951-YR328
0513	22		CQ		8-0	27-62-11		D40668P				D40632P	13			YC051-YD158, YL951-YR328
0514	22		CQ		8-0	27-62-11		D40668P				D40632P	14			YC051-YD158, YL951-YR328
0515	22		CQ		8-0	27-62-11		D40668P				D40632P	15			YC051-YD158, YL951-YR328
0518	22		PA		14-6	29-23-11		D40668P				D40698P	7			YC051-YD158, YL951-YR328
0521	22		PA		8-0	32-31-11		D40632P				D40668P	9			YC051-YD158, YL951-YR328
0601	22		PA		13-11	32-31-12		D40698P				D40632P	21			YC051-YD158, YL951-YR328
0602	22		CQ		13-11	32-31-12		D40698P				D40632P	1			YC051-YD158, YL951-YR328
0604	22		CQ		13-11	32-31-12		D40698P				D40632P	2			YC051-YD158, YL951-YR328
0605	22		CQ		13-11	32-31-12		D40698P				D40632P	3			YC051-YD158, YL951-YR328
0606	22		CQ		13-11	32-31-12		D40698P				D40632P	4			YC051-YD158, YL951-YR328
0607	22		CQ		13-11	32-31-12		D40698P				D40632P	5			YC051-YD158, YL951-YR328
0631	22		PA		14-6	32-41-11		D40698P				D40668P	1			YC051-YD158, YL951-YR328
2004B	24		7K	GD	14-6	34-49-11		D40668P				D40698P	28			YC053-YD158, YL951-YR328
2004W	24		7K	GD	0-0	34-49-11		D40668P				D40698P	27			YC053-YD158, YL951-YR328
2004Z				GD	0-0	34-49-11		D40668P			GD	D40698P			VT	YC053-YD158, YL951-YR328
2601B	24		7K	SA	14-6	34-41-11		D40668P				D40698P	17			YC053-YD158, YL951-YR328
2601W	24		7K	SA	0-0	34-41-11		D40668P				D40698P	16			YC053-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5100

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Fam	Description FT-IN Diagram		From Equip Term Type Splice			To Equip Term Type Splice Effectivity						
W5100	286A5100				J24 TO J20 & J22: J-BOX INTERCONNECT BUNDLE (continued)											
2601Z				SA	0-0	34-41-11	D40668P			SA	D40698P			VZ	YC053-YD158, YL951-YR328	
2602B	24	7K	SB		14-6	34-41-11	D40668P	27			D40698P	19			YC053-YD158, YL951-YR328	
2602W	24	7K	SB		0-0	34-41-11	D40668P	26			D40698P	18			YC053-YD158, YL951-YR328	
2602Z				SB	0-0	34-41-11	D40668P			SB	D40698P			VY	YC053-YD158, YL951-YR328	
6001R	22	PH			14-6	SPARE	D40668P	8			D40698P	8			YC051-YD158, YL951-YR328	
6002R	22	PH			14-6	SPARE	D40668P	20			D40698P	20			YC051-YD158, YL951-YR328	
6003R	22	PH			14-6	SPARE	D40668P	21			D40698P	21			YC051-YD158, YL951-YR328	
FRG1					0-0	34-49-11	D40668P			GD	D40668P	S/R			YC053-YD158, YL951-YR328	
FRG2					0-0	34-49-11	D40698P			VT	D40698P	S/R			YC053-YD158, YL951-YR328	
FRGD					0-0	34-49-11	D40668P	28			D40668P			GD	YC053-YD158, YL951-YR328	
FRSA					0-0	34-41-11	D40668P	22			D40668P			SA	YC053-YD158, YL951-YR328	
FRSB					0-0	34-41-11	D40668P	25			D40668P			SB	YC053-YD158, YL951-YR328	
FRVT					0-0	34-49-11	D40698P	29			D40698P			VT	YC053-YD158, YL951-YR328	
FRVU					0-0	34-41-11	D40698P			VY	D40698P	S/R			YC053-YD158, YL951-YR328	
FRVV					0-0	34-41-11	D40668P			SB	D40668P	S/R			YC053-YD158, YL951-YR328	
FRVW					0-0	34-41-11	D40698P			VZ	D40698P	S/R			YC053-YD158, YL951-YR328	
FRVX					0-0	34-41-11	D40668P			SA	D40668P	S/R			YC053-YD158, YL951-YR328	
FRVY					0-0	34-41-11	D40698P	23			D40698P			VY	YC053-YD158, YL951-YR328	
FRVZ					0-0	34-41-11	D40698P	22			D40698P			VZ	YC053-YD158, YL951-YR328	

WIRE LIST

D280A108

91-21-11

Section W5100

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From						To					
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I	W5101	286A5101			AUDIO ENTERTAINMENT - AUDIO INTEGRATION BRKT AB0410 TO SIDEWALL DISC'S											
	0001	22		PA		35-2	23-34-02	D12169J				D08427J	11			YL951-YL999
	0001	22		PA		35-0	23-34-02	D12169J				D08427J	11			YN231-YN260
	0001	22		PA		35-0	44-21-26	D12169J				D08427J	11			YN501
I	0001	22		PA		35-2	44-21-26	D12169J				D08427J	11			YR301-YR328
	0002	22		PA		35-2	23-34-02	D12169J				D08427J	10			YL951-YL999
	0002	22		PA		35-0	23-34-02	D12169J				D08427J	10			YN231-YN260
	0002	22		PA		35-0	44-21-26	D12169J				D08427J	10			YN501
I	0002	22		PA		35-2	44-21-26	D12169J				D08427J	10			YR301-YR328
	0003	22		PA		14-6	23-34-02	D12169J				D08429J	11			YL951-YN260
I	0003	22		PA		14-6	44-21-26	D12169J				D08429J	11			YN501-YR328
	0004	22		PA		14-6	23-34-02	D12169J				D08429J	10			YL951-YN260
I	0004	22		PA		14-6	44-21-26	D12169J				D08429J	10			YN501-YR328
	0005	22		PA		64-8	23-34-02	D12171J				D08537J	10			YL951-YL999
	0005	22		PA		54-5	23-34-02	D12171J				D08537J	10			YN231-YN260
	0005	22		PA		54-5	44-21-26	D12171J				D08537J	10			YN501
I	0005	22		PA		64-8	44-21-26	D12171J				D08537J	10			YR301-YR328
	0009	22		PA		73-6	23-34-02	D12171J				D08539J	10			YL951-YL999
	0009	22		PA		63-7	23-34-02	D12171J				D08539J	10			YN231-YN260
	0009	22		PA		63-7	44-21-26	D12171J				D08539J	10			YN501
I	0009	22		PA		73-6	44-21-26	D12171J				D08539J	10			YR301-YR328
	2501B	24		OT	AA	35-2	23-34-02	D12169J				D08427J	4			YL951-YL999
	2501B	24		OT	AA	35-0	MULTI	D12169J				D08427J	4			YN231-YN260
	2501B	24		OT	AA	35-0	44-21-26	D12169J				D08427J	4			YN501
I	2501B	24		OT	AA	35-2	44-21-26	D12169J				D08427J	4			YR301-YR328
	2501W	24		OT	AA	0-0	23-34-02	D12169J				D08427J	5			YL951-YL999
	2501W	24		OT	AA	0-0	MULTI	D12169J				D08427J	5			YN231-YN260
I	2501W	24		OT	AA	0-0	44-21-26	D12169J				D08427J	5			YN501-YR328
	2501Z				AA	0-0	23-34-02	D12169J	PERS	1A		D08427J	PERB			YL951-YL999
	2501Z				AA	0-0	MULTI	D12169J	PERS	1A		D08427J	PERB			YN231-YN260
I	2501Z				AA	0-0	44-21-26	D12169J	PERS	1A		D08427J	PERB			YN501-YR328
	2502B	24		OT	AB	35-2	23-34-02	D12169J				D08427J	2			YL951-YL999
	2502B	24		OT	AB	35-0	MULTI	D12169J				D08427J	2			YN231-YN260
	2502B	24		OT	AB	35-0	44-21-26	D12169J				D08427J	2			YN501
I	2502B	24		OT	AB	35-2	44-21-26	D12169J				D08427J	2			YR301-YR328
	2502W	24		OT	AB	0-0	23-34-02	D12169J				D08427J	1			YL951-YL999
	2502W	24		OT	AB	0-0	MULTI	D12169J				D08427J	1			YN231-YN260
I	2502W	24		OT	AB	0-0	44-21-26	D12169J				D08427J	1			YN501-YR328
	2502Z				AB	0-0	23-34-02	D12169J	PERS	1A		D08427J			AB	YL951-YL999
	2502Z				AB	0-0	MULTI	D12169J	PERS	1A		D08427J			AB	YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W5100

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5101	286A5101				AUDIO ENTERTAINMENT - AUDIO INTEGRATION BRKT AB0410 TO SIDEWALL DISC'S (continued)										
2502Z				AB	0-0	44-21-26	D12169J	PERS	1A		D08427J			AB	YN501-YR328
2503B	24	OT	AC		35-2	23-34-02	D12169J	14			D08427J	8			YL951-YL999
2503B	24	OT	AC		35-0	MULTI	D12169J	14			D08427J	8			YN231-YN260
2503B	24	OT	AC		35-0	44-21-26	D12169J	14			D08427J	8			YN501
2503B	24	OT	AC		35-2	44-21-26	D12169J	14			D08427J	8			YR301-YR328
2503W	24	OT	AC		0-0	23-34-02	D12169J	13			D08427J	7			YL951-YL999
2503W	24	OT	AC		0-0	MULTI	D12169J	13			D08427J	7			YN231-YN260
2503W	24	OT	AC		0-0	44-21-26	D12169J	13			D08427J	7			YN501-YR328
2503Z			AC		0-0	23-34-02	D12169J	PERS	1A		D08427J			AC	YL951-YL999
2503Z			AC		0-0	MULTI	D12169J	PERS	1A		D08427J			AC	YN231-YN260
2503Z			AC		0-0	44-21-26	D12169J	PERS	1A		D08427J			AC	YN501-YR328
2504B	20	X2	AD		35-2	23-34-02	D12169J	8			D08427J	15			YL951-YL999
2504B	20	X2	AD		35-0	MULTI	D12169J	8			D08427J	15			YN231-YN260
2504B	20	X2	AD		35-0	44-21-26	D12169J	8			D08427J	15			YN501
2504B	20	X2	AD		35-2	44-21-26	D12169J	8			D08427J	15			YR301-YR328
2504R	20	X2	AD		0-0	23-34-02	D12169J	7			D08427J	14			YL951-YL999
2504R	20	X2	AD		0-0	MULTI	D12169J	7			D08427J	14			YN231-YN260
2504R	20	X2	AD		0-0	44-21-26	D12169J	7			D08427J	14			YN501-YR328
2504Z			AD		0-0	23-34-02	D12169J	PERS	1A		D08427J	PERB			YL951-YL999
2504Z			AD		0-0	MULTI	D12169J	PERS	1A		D08427J	PERB			YN231-YN260
2504Z			AD		0-0	44-21-26	D12169J	PERS	1A		D08427J	PERB			YN501-YR328
2505B	24	OT	AE		14-6	23-34-02	D12169J	27			D08429J	4			YL951-YL999
2505B	24	OT	AE		14-6	MULTI	D12169J	27			D08429J	4			YN231-YN260
2505B	24	OT	AE		14-6	44-21-26	D12169J	27			D08429J	4			YN501-YR328
2505W	24	OT	AE		0-0	23-34-02	D12169J	26			D08429J	5			YL951-YL999
2505W	24	OT	AE		0-0	MULTI	D12169J	26			D08429J	5			YN231-YN260
2505W	24	OT	AE		0-0	44-21-26	D12169J	26			D08429J	5			YN501-YR328
2505Z			AE		0-0	23-34-02	D12169J	PERS	1A		D08429J	PERB			YL951-YL999
2505Z			AE		0-0	MULTI	D12169J	PERS	1A		D08429J	PERB			YN231-YN260
2505Z			AE		0-0	44-21-26	D12169J	PERS	1A		D08429J	PERB			YN501-YR328
2506B	24	OT	AF		14-6	23-34-02	D12169J	29			D08429J	2			YL951-YL999
2506B	24	OT	AF		14-6	MULTI	D12169J	29			D08429J	2			YN231-YN260
2506B	24	OT	AF		14-6	44-21-26	D12169J	29			D08429J	2			YN501-YR328
2506W	24	OT	AF		0-0	23-34-02	D12169J	28			D08429J	1			YL951-YL999
2506W	24	OT	AF		0-0	MULTI	D12169J	28			D08429J	1			YN231-YN260
2506W	24	OT	AF		0-0	44-21-26	D12169J	28			D08429J	1			YN501-YR328
2506Z			AF		0-0	23-34-02	D12169J	PERS	1A		D08429J			AF	YL951-YL999
2506Z			AF		0-0	MULTI	D12169J	PERS	1A		D08429J			AF	YN231-YN260
2506Z			AF		0-0	44-21-26	D12169J	PERS	1A		D08429J			AF	YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W5100

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Diagram	From	To			Effectivity				
	Wire No.	GA	CO TY			Fam	FT-IN	Equip	Term		Type	Splice	Equip	Term
W5101	286A5101			AUDIO ENTERTAINMENT - AUDIO INTEGRATION BRKT AB0410 TO SIDEWALL DISC'S (continued)										
2507B	24	OT	AG	14-6	23-34-02	D12169J	31			D08429J	8			YL951-YL999
2507B	24	OT	AG	14-6	MULTI	D12169J	31			D08429J	8			YN231-YN260
2507B	24	OT	AG	14-6	44-21-26	D12169J	31			D08429J	8			YN501-YR328
2507W	24	OT	AG	0-0	23-34-02	D12169J	30			D08429J	7			YL951-YL999
2507W	24	OT	AG	0-0	MULTI	D12169J	30			D08429J	7			YN231-YN260
2507W	24	OT	AG	0-0	44-21-26	D12169J	30			D08429J	7			YN501-YR328
2507Z			AG	0-0	23-34-02	D12169J	PERS	1A		D08429J			AG	YL951-YL999
2507Z			AG	0-0	MULTI	D12169J	PERS	1A		D08429J			AG	YN231-YN260
2507Z			AG	0-0	44-21-26	D12169J	PERS	1A		D08429J			AG	YN501-YR328
2508B	20	X2	AH	14-6	23-34-02	D12169J	25			D08429J	15			YL951-YL999
2508B	20	X2	AH	14-6	MULTI	D12169J	25			D08429J	15			YN231-YN260
2508B	20	X2	AH	14-6	44-21-26	D12169J	25			D08429J	15			YN501-YR328
2508R	20	X2	AH	0-0	23-34-02	D12169J	24			D08429J	14			YL951-YL999
2508R	20	X2	AH	0-0	MULTI	D12169J	24			D08429J	14			YN231-YN260
2508R	20	X2	AH	0-0	44-21-26	D12169J	24			D08429J	14			YN501-YR328
2508Z			AH	0-0	23-34-02	D12169J	PERS	1A		D08429J	PERB			YL951-YL999
2508Z			AH	0-0	MULTI	D12169J	PERS	1A		D08429J	PERB			YN231-YN260
2508Z			AH	0-0	44-21-26	D12169J	PERS	1A		D08429J	PERB			YN501-YR328
2509B	24	OT	AI	64-8	23-34-02	D12171J	10			D08537J	4			YL951-YL999
2509B	24	OT	AI	54-5	MULTI	D12171J	10			D08537J	4			YN231-YN260
2509B	24	OT	AI	54-5	44-21-26	D12171J	10			D08537J	4			YN501
2509B	24	OT	AI	64-8	44-21-26	D12171J	10			D08537J	4			YR301-YR328
2509W	24	OT	AI	0-0	23-34-02	D12171J	9			D08537J	5			YL951-YL999
2509W	24	OT	AI	0-0	MULTI	D12171J	9			D08537J	5			YN231-YN260
2509W	24	OT	AI	0-0	44-21-26	D12171J	9			D08537J	5			YN501-YR328
2509Z			AI	0-0	23-34-02	D12171J	PERS	1A		D08537J	PERB			YL951-YL999
2509Z			AI	0-0	MULTI	D12171J	PERS	1A		D08537J	PERB			YN231-YN260
2509Z			AI	0-0	44-21-26	D12171J	PERS	1A		D08537J	PERB			YN501-YR328
2510B	24	OT	AJ	64-8	23-34-02	D12171J	12			D08537J	2			YL951-YL999
2510B	24	OT	AJ	54-5	MULTI	D12171J	12			D08537J	2			YN231-YN260
2510B	24	OT	AJ	54-5	44-21-26	D12171J	12			D08537J	2			YN501
2510B	24	OT	AJ	64-8	44-21-26	D12171J	12			D08537J	2			YR301-YR328
2510W	24	OT	AJ	0-0	23-34-02	D12171J	11			D08537J	1			YL951-YL999
2510W	24	OT	AJ	0-0	MULTI	D12171J	11			D08537J	1			YN231-YN260
2510W	24	OT	AJ	0-0	44-21-26	D12171J	11			D08537J	1			YN501-YR328
2510Z			AJ	0-0	23-34-02	D12171J	PERS	1A		D08537J	PERB			YL951-YL999
2510Z			AJ	0-0	MULTI	D12171J	PERS	1A		D08537J	PERB			YN231-YN260
2510Z			AJ	0-0	44-21-26	D12171J	PERS	1A		D08537J	PERB			YN501-YR328
2511B	20	X2	AK	64-8	23-34-02	D12171J	8			D08537J	15			YL951-YL999

WIRE LIST

D280A108

91-21-11

Section W5100

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5101	286A5101			AUDIO ENTERTAINMENT - AUDIO INTEGRATION BRKT AB0410 TO SIDEWALL DISC'S (continued)											
2511B	20	X2	AK		54-5	MULTI	D12171J	8			D08537J	15			YN231-YN260
2511B	20	X2	AK		54-5	44-21-26	D12171J	8			D08537J	15			YN501
2511B	20	X2	AK		64-8	44-21-26	D12171J	8			D08537J	15			YR301-YR328
2511R	20	X2	AK		0-0	23-34-02	D12171J	7			D08537J	14			YL951-YL999
2511R	20	X2	AK		0-0	MULTI	D12171J	7			D08537J	14			YN231-YN260
2511R	20	X2	AK		0-0	44-21-26	D12171J	7			D08537J	14			YN501-YR328
2511Z			AK		0-0	23-34-02	D12171J	PERS	1A		D08537J	PERB			YL951-YL999
2511Z			AK		0-0	MULTI	D12171J	PERS	1A		D08537J	PERB			YN231-YN260
2511Z			AK		0-0	44-21-26	D12171J	PERS	1A		D08537J	PERB			YN501-YR328
2512B	24	OT	AL		73-6	23-34-02	D12171J	27			D08539J	4			YL951-YL999
2512B	24	OT	AL		63-7	MULTI	D12171J	27			D08539J	4			YN231-YN260
2512B	24	OT	AL		63-7	44-21-26	D12171J	27			D08539J	4			YN501
2512B	24	OT	AL		73-6	44-21-26	D12171J	27			D08539J	4			YR301-YR328
2512W	24	OT	AL		0-0	23-34-02	D12171J	26			D08539J	5			YL951-YL999
2512W	24	OT	AL		0-0	MULTI	D12171J	26			D08539J	5			YN231-YN260
2512W	24	OT	AL		0-0	44-21-26	D12171J	26			D08539J	5			YN501-YR328
2512Z			AL		0-0	23-34-02	D12171J	PERS	1A		D08539J	PERB			YL951-YL999
2512Z			AL		0-0	MULTI	D12171J	PERS	1A		D08539J	PERB			YN231-YN260
2512Z			AL		0-0	44-21-26	D12171J	PERS	1A		D08539J	PERB			YN501-YR328
2513B	24	OT	AM		73-6	23-34-02	D12171J	29			D08539J	2			YL951-YL999
2513B	24	OT	AM		63-7	MULTI	D12171J	29			D08539J	2			YN231-YN501
2513B	24	OT	AM		73-6	44-21-26	D12171J	29			D08539J	2			YR301-YR328
2513W	24	OT	AM		0-0	23-34-02	D12171J	28			D08539J	1			YL951-YL999
2513W	24	OT	AM		0-0	MULTI	D12171J	28			D08539J	1			YN231-YN501
2513W	24	OT	AM		0-0	44-21-26	D12171J	28			D08539J	1			YR301-YR328
2513Z			AM		0-0	23-34-02	D12171J	PERS	1A		D08539J	PERB			YL951-YL999
2513Z			AM		0-0	MULTI	D12171J	PERS	1A		D08539J	PERB			YN231-YN501
2513Z			AM		0-0	44-21-26	D12171J	PERS	1A		D08539J	PERB			YR301-YR328
2514B	20	X2	AN		73-6	23-34-02	D12171J	25			D08539J	15			YL951-YL999
2514B	20	X2	AN		63-7	MULTI	D12171J	25			D08539J	15			YN231-YN260
2514B	20	X2	AN		63-7	44-21-26	D12171J	25			D08539J	15			YN501
2514B	20	X2	AN		73-6	44-21-26	D12171J	25			D08539J	15			YR301-YR328
2514R	20	X2	AN		0-0	23-34-02	D12171J	24			D08539J	14			YL951-YL999
2514R	20	X2	AN		0-0	MULTI	D12171J	24			D08539J	14			YN231-YN260
2514R	20	X2	AN		0-0	44-21-26	D12171J	24			D08539J	14			YN501-YR328
2514Z			AN		0-0	23-34-02	D12171J	PERS	1A		D08539J	PERB			YL951-YL999
2514Z			AN		0-0	MULTI	D12171J	PERS	1A		D08539J	PERB			YN231-YN260
2514Z			AN		0-0	44-21-26	D12171J	PERS	1A		D08539J	PERB			YN501-YR328
FRAB					0-0	23-34-02	D08427J			AB	D08427J	3			YL951-YN260

WIRE LIST

D280A108

91-21-11

Section W5100

Page 7

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W5101	286A5101				AUDIO ENTERTAINMENT - AUDIO INTEGRATION BRKT AB0410 TO SIDEWALL DISC'S (continued)												
	FRAB				0-0	44-21-26	D08427J					AB	D08427J	3		YN501-YR328	
	FRAC				0-0	23-34-02	D08427J					AC	D08427J	6		YL951-YN260	
	FRAC				0-0	44-21-26	D08427J					AC	D08427J	6		YN501-YR328	
	FRAF				0-0	23-34-02	D08429J					AF	D08429J	3		YL951-YN260	
	FRAF				0-0	44-21-26	D08429J					AF	D08429J	3		YN501-YR328	
	FRAG				0-0	23-34-02	D08429J					AG	D08429J	6		YL951-YN260	
	FRAG				0-0	44-21-26	D08429J					AG	D08429J	6		YN501-YR328	
	FRBB				0-0	23-34-02	D08427J					AB	D08427J	PERB		YL951-YN260	
	FRBB				0-0	44-21-26	D08427J					AB	D08427J	PERB		YN501-YR328	
	FRBC				0-0	23-34-02	D08427J					AC	D08427J	PERB		YL951-YN260	
	FRBC				0-0	44-21-26	D08427J					AC	D08427J	PERB		YN501-YR328	
	FRBF				0-0	23-34-02	D08429J					AF	D08429J	PERB		YL951-YN260	
	FRBF				0-0	44-21-26	D08429J					AF	D08429J	PERB		YN501-YR328	
	FRBG				0-0	23-34-02	D08429J					AG	D08429J	PERB		YL951-YN260	
	FRBG				0-0	44-21-26	D08429J					AG	D08429J	PERB		YN501-YR328	
	YAAA				0-0	23-34-02	D12169J			PERB			OAS0001			YL951-YN260	
	YAAA				0-0	44-21-26	D12169J			PERB			OAS0001			YN501-YR328	
	YAAB				0-0	23-34-02	D08427J			PERB			OAS0001			YL951-YN260	
	YAAB				0-0	44-21-26	D08427J			PERB			OAS0001			YN501-YR328	
	YAAC				0-0	23-34-02	D08429J			PERB			OAS0001			YL951-YN260	
	YAAC				0-0	44-21-26	D08429J			PERB			OAS0001			YN501-YR328	
	YAAD				0-0	23-34-02	D12171J			PERB			OAS0002			YL951-YN260	
	YAAD				0-0	44-21-26	D12171J			PERB			OAS0002			YN501-YR328	
	YAAE				0-0	23-34-02	D08537J			PERB			OAS0002			YL951-YN260	
	YAAE				0-0	44-21-26	D08537J			PERB			OAS0002			YN501-YR328	
	YAAF				0-0	23-34-02	D08539J			PERB			OAS0002			YL951-YN260	
	YAAF				0-0	44-21-26	D08539J			PERB			OAS0002			YN501-YR328	
W5102	286A5102				LEFT A/C PACK (STA 536L) DISC TO A/C PACK (SA2)												
	0003	20		HA	0-7	33-33-11	S00066		1	G7	*		S00066	4	G7	YC051-YN236, YN501-YR328	
	0005	20		HA	1-8	33-33-11	SM00002			9			S00066	5	G7	* YC051-YL999, YR301-YR328	
	0005	20		HA	1-5	33-33-11	SM00002			9			S00066	5	G7	* YN231-YN236, YN501	
	0006	20		HA	4-9	33-33-11	SM00002			9			L00177	=P	BK	YC051-YL999, YR301-YR328	
	0006	20		HA	4-2	33-33-11	SM00002			9			L00177	=P	BK	YN231-YN236, YN501	
	0007	20		HA	3-4	33-33-11	L00176		=P	BK			SM00002	9		YC051-YL999, YR301-YR328	

WIRE LIST

D280A108

91-21-11

Section W5100

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Description Fam	Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W5102	286A5102			LEFT A/C PACK (STA 536L) DISC TO A/C PACK (SA2) (continued)										
0007	20	HA		3-3	33-33-11	L00176	=P	BK		SM00002		9		YN231-YN236, YN501
0009	20	HA		11-6	33-33-11	SM00002		9		L00178	=P	BK		YC051-YL999, YR301-YR328
0009	20	HA		11-7	33-33-11	SM00002		9		L00178	=P	BK		YN231-YN236, YN501
0010	20	HA		0-7	21-51-16	TB0536Y	A001	1A		TB0536Y	B003	1A		YN231-YN236, YN501
0011	20	HA		1-8	33-33-11	GD05128	AC..	GW		L00177	=G	G7		YC051-YL999, YR301-YR328
0011	20	HA		6-10	33-33-11	GD02322	AC..	GW		L00177	=G	G7		YN231-YN236, YN501
0012	20	HA		1-11	33-33-11	GD02322	AC..	GW		L00176	=G	G7		YC051-YL999, YR301-YR328
0012	20	HA		2-0	33-33-11	GD02322	AC..	GW		L00176	=G	G7		YN231-YN236, YN501
0014	20	HA		1-10	33-33-11	GD00552	AC..	GW		L00178	=G	G7		YC051-YN236, YN501-YR328
0015	20	HA		1-9	21-51-12	D03862		13		GD05122	ST..	GW		YD154-YL999, YR301-YR328
1001	20	HE	AA	7-7	21-51-15	D04580J		7		D00532		2		YC051-YD157
1001	20	HE	AA	7-8	21-51-15	D04580J		7		D00532		2		YD158-YL999, YR301-YR328
1001	20	HE	AA	7-1	21-51-15	D04580J		7		D00532		2		YN231-YN236, YN501
1001Z			AA	0-0	21-51-15	D04580J	S/R			D00532			AD	YC051-YD153
1001Z			AA	0-0	21-51-15	D04580J	S/R			GD05130	ST..	GW	*3	YD154-YL999, YR301-YR328
1001Z			AA	0-0	21-51-15	D04580J	S/R			GD02312	ST..	GW		YN231-YN236, YN501
1002	20	HE	AB	6-7	21-51-15	D04580J		5		D00530		2		YN231-YN236, YN501
1002Z			AB	0-0	21-51-15	D04580J	S/R			GD02308	ST..	GW		YN231-YN236, YN501
1003	20	HE	AC	3-6	21-51-15	GD02316	DC..	GW	*2	D00530		1		YN231-YN236, YN501
1003Z			AC	0-0	21-51-15	GD02316	DC..	GW	*2	GD02308	ST..	GW		YN231-YN236, YN501
1005	20	HE	AE	3-3	21-51-15	GD02316	DC..	GW	*1	D00532		1		YC051-YD157
1005	20	HE	AE	3-4	21-51-15	GD02316	DC..	GW	*1	D00532		1		YD158-YL999, YR301-YR328
1005	20	HE	AE	3-0	21-51-15	GD02316	DC..	GW	*1	D00532		1		YN231-YN236, YN501
1005Z			AE	0-0	21-51-15	GD02316	DC..	GW	*1	D00532			AD	YC051-YD153
1005Z			AE	0-0	21-51-15	GD02316	DC..	GW	*1	GD05130	ST..	GW	*3	YD154-YL999, YR301-YR328
1005Z			AE	0-0	21-51-15	GD02316	DC..	GW	*1	GD02312	ST..	GW		YN231-YN236, YN501
1006	20	HE	AF	5-3	21-51-14	D00970		5		GD00012	AC..	1		YN231-YN236, YN501
1006Z			AF	0-0	21-51-14	GD02316	ST..	GW	*4	GD00012	ST..	1		YN231-YN236, YN501
1007	20	HE	AG	5-1	21-51-14	D00970		4		D40056J		1		YN231-YN236, YN501
1007Z			AG	0-0	21-51-14	GD02316	ST..	GW	*4	D40056J	S/R			YN231-YN236, YN501

WIRE LIST

D280A108

91-21-11

Section W5100

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY	Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice
W5102	286A5102	LEFT A/C PACK (STA 536L) DISC TO A/C PACK (SA2) (continued)			
1008	20	HE	AH	6-5 21-51-16 D40056J	14 D00706
1008Z			AH	0-0 21-51-16 D40056J	S/R GD02314
1009	20	HE	AI	2-3 21-51-16 GD01154	AC.. GW *1 D00706
1009Z			AI	0-0 21-51-16 GD01154	AC.. GW *1 GD02314
1010	20	HE	AJ	6-11 21-51-16 D00702	3 GD00012
1010Z			AJ	0-0 21-51-16 GD02310	ST.. GW 1 GD00012
1013R	20	H9	AM	14-7 26-12-11 M01911	=B GW D04580J
1013R	20	H9	AM	14-6 26-12-11 M01911	=B GW D04580J
1013Z			AM	0-0 26-12-11 GD02302	ST.. GW *1 D04580J
1014R	20	H9	AN	4-9 26-12-11 D00858	=1 D04580J
1014R	20	H9	AN	4-10 26-12-11 D00858	=1 D04580J
1014Z			AN	0-0 26-12-11 GD02316	DC.. GW D04580J
1015R	20	H9	AP	5-1 26-12-11 D00832	=1 D04580J
1015R	20	H9	AP	4-0 26-12-11 D00832	=1 D04580J
1015Z			AP	0-0 26-12-11 GD02320	ST.. GW D04580J
1015Z			AP	0-0 26-12-11 GD02320	ST.. GW *1 D04580J
1016	20	HE	AQ	2-4 33-33-11 S00066	2 G7 * D04580J
1016	20	HE	AQ	2-6 33-33-11 S00066	2 G7 * D04580J
1016Z			AQ	0-0 33-33-11 GD02318	ST.. GW *1 D04580J
1017	20	HE	AR	2-4 33-33-11 S00066	5 G7 * D04580J
1017	20	HE	AR	2-6 33-33-11 S00066	5 G7 * D04580J
1017Z			AR	0-0 33-33-11 GD02318	ST.. GW *1 D04580J
1018	20	HE	AS	2-4 33-33-11 D04580J	4 S00066
1018	20	HE	AS	2-6 33-33-11 D04580J	4 S00066
1018Z			AS	0-0 33-33-11 D04580J	S/R GD02318
1019	20	HE	AT	2-4 33-33-11 D04580J	3 S00066

WIRE LIST

D280A108

91-21-11

Section W5100

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Description Fam	Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W5102	286A5102			LEFT A/C PACK (STA 536L) DISC TO A/C PACK (SA2) (continued)										
1019	20	HE	AT	2-6	33-33-11	D04580J	3			S00066	1	G7	*	YN231-YN236, YN501
1019Z			AT	0-0	33-33-11	D04580J	S/R			GD02318	ST..	GW	*2	YC051-YN236, YN501-YR328
1025R	20	H9	AZ	14-7	26-12-11	M01911	= A	GW		D04580J	11			YC051-YN236, YN501-YR328
1025Z			AZ	0-0	26-12-11	GD02302	ST..	GW	*1	D04580J	S/R			YC051-YN236, YN501-YR328
1026	20	HE	BA	1-9	21-51-12	D03862	13			GD05122	ST..	GW	*1	YC051-YD153
1026Z			BA	0-0	21-51-12	D03862			AH	GD05122	ST..	GW	*1	YC051-YD153
1027	20	HE	BB	2-10	21-51-12	D03862	3			GD05124	AC..	GW	*1	YC051-YL999, YR301-YR328
1027Z			BB	0-0	21-51-12	D03862			AH	GD05124	AC..	GW	*1	YC051-YD153
1027Z			BB	0-0	21-51-12	GD05122	ST..	GW	*	GD05124	AC..	GW	*1	YD154-YL999, YR301-YR328
1028	20	HE	BC	2-6	21-51-12	D03862	5			GD00382	DC..	GW	*1	YC051-YL999, YR301-YR328
1028Z			BC	0-0	21-51-12	D03862			AH	GD00382	DC..	GW	*1	YC051-YD153
1028Z			BC	0-0	21-51-12	GD05122	ST..	GW	*	GD00382	DC..	GW	*1	YD154-YL999, YR301-YR328
1030	20	HE	BE	4-2	36-21-11	D00100	3			D40056J	11			YC051-YL999, YR301-YR328
1030	20	HE	BE	6-0	36-21-11	D00100	3			D40056J	11			YN231-YN236, YN501
1030Z			BE	0-0	36-21-11	GD02320	ST..	GW		D40056J	S/R			YC051-YL999, YR301-YR328
1030Z			BE	0-0	36-21-11	GD02320	ST..	GW	*1	D40056J	S/R			YN231-YN236, YN501
1033	20	HE	BH	7-5	21-51-15	D04580J	6			D10056	2			YC051-YD157
1033	20	HE	BH	7-6	21-51-15	D04580J	6			D10056	2			YD158-YL999, YR301-YR328
1033Z			BH	0-0	21-51-15	D04580J	S/R			GD05130	ST..	GW	*1	YC051-YL999, YR301-YR328
1034	20	HE	BI	3-1	21-51-15	D10056	1			GD02316	DC..	GW	*2	YC051-YD157
1034	20	HE	BI	3-2	21-51-15	D10056	1			GD02316	DC..	GW	*2	YD158-YL999, YR301-YR328
1034Z			BI	0-0	21-51-15	GD05130	ST..	GW	*1	GD02316	DC..	GW	*2	YC051-YL999, YR301-YR328
1049	20	HE	CA	7-7	21-61-51	D03930	B			D40056J	30			YC051-YL999, YR301-YR328
1049Z			CA	0-0	21-61-51	GD05130	ST..	GW	*2	D40056J	S/R			YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W5100

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY	Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice
W5102	286A5102	LEFT A/C PACK (STA 536L) DISC TO A/C PACK (SA2) (continued)			
1050	20	HE CB	3-9 21-61-51	D03930 A	GD02316 DC.. GW *3 YC051-YD157
1050	20	HE CB	3-3 21-61-51	D03930 A	GD02316 DC.. GW *3 YD158-YL999, YR301-YR328
1050Z		CB	0-0 21-61-51	GD05130 ST.. GW *2	GD02316 DC.. GW *3 YC051-YL999, YR301-YR328
1201	20	HE DA	14-9 33-44-11	D40056J 15	D11050 1 YC051-YD158
1201	20	HE DA	14-1 33-44-11	D40056J 15	D11050 1 YD160-YN236, YN501-YR328
1201Z		DA	0-0 33-44-11	D40056J S/R	D11050 S/R YC051-YN236, YN501-YR328
1202	20	HE DB	4-6 33-44-11	D11050 2	GD00552 AC.. GW *1 YC051-YD158
1202	20	HE DB	3-10 33-44-11	D11050 2	GD00552 AC.. GW *1 YD160-YL999, YR301-YR328
1202	20	HE DB	4-1 33-44-11	D11050 2	GD00552 AC.. GW *1 YN231-YN236, YN501
1202Z		DB	0-0 33-44-11	D11050 S/R	GD00552 AC.. GW *1 YC051-YN236, YN501-YR328
1203	20	HE DC	4-3 33-44-11	D11050 3	GD04308 ST.. GW *1 YC051-YD158
1203	20	HE DC	3-7 33-44-11	D11050 3	GD04308 ST.. GW *1 YD160-YL999, YR301-YR328
1203	20	HE DC	3-8 33-44-11	D11050 3	GD04308 ST.. GW *1 YN231-YN236, YN501
1203Z		DC	0-0 33-44-11	D11050 S/R	GD04308 ST.. GW *1 YC051-YN236, YN501-YR328
2001B	20	HF GA	4-0 21-51-14	D00970 6	D01288 1 YN231-YN236, YN501
2001R	20	HF GA	0-0 21-51-14	D00970 7	D01288 2 YN231-YN236, YN501
2001Z		GA	0-0 21-51-14	GD02316 ST.. GW *4	GD02308 ST.. GW YN231-YN236, YN501
2002B	20	HF GB	5-1 21-51-14	D00970 2	D40056J 2 YN231-YN236, YN501
2002R	20	HF GB	0-0 21-51-14	D00970 3	D40056J 3 YN231-YN236, YN501
2002Z		GB	0-0 21-51-14	GD02316 ST.. GW *4	D40056J S/R YN231-YN236, YN501
2003B	20	HF GC	4-0 21-51-16	D00702 1	D00706 2 YN231-YN236, YN501
2003R	20	HF GC	0-0 21-51-16	D00702 2	D00706 3 YN231-YN236, YN501
2003Z		GC	0-0 21-51-16	GD02310 ST.. GW	GD02314 ST.. GW YN231-YN236, YN501
2005B	20	HF GE	16-6 21-61-21	D00172 2	D40056J 8 YN231-YN236, YN501
2005R	20	HF GE	0-0 21-61-21	D00172 3	D40056J 9 YN231-YN236, YN501
2005Z		GE	0-0 21-61-21	GD02300 ST.. GW	D40056J S/R YN231-YN236, YN501
2006B	20	HF GF	16-2 21-61-21	D00524 1	D40056J 6 YN231-YN236, YN501
2006R	20	HF GF	0-0 21-61-21	D00524 2	D40056J 7 YN231-YN236, YN501
2006Z		GF	0-0 21-61-21	GD02300 ST.. GW	D40056J S/R YN231-YN236, YN501
2007B	20	HF GG	4-2 36-21-11	D00100 2	D40056J 13 YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W5100

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5102	286A5102			LEFT A/C PACK (STA 536L) DISC TO A/C PACK (SA2) (continued)											
2007B	20	HF	GG		6-0	36-21-11	D00100	2			D40056J	13			YN231-YN236, YN501
2007R	20	HF	GG		0-0	36-21-11	D00100	1			D40056J	12			YC051-YN236, YN501-YR328
2007Z			GG		0-0	36-21-11	GD02320	ST..	GW	*1	D40056J	S/R			YC051-YN236, YN501-YR328
2076B	20	HF	JA		17-5	21-51-12	D40056J	1			D03862	11			YC051-YL999, YR301-YR328
2076R	20	HF	JA		0-0	21-51-12	D40056J	2			D03862	10			YC051-YL999, YR301-YR328
2076Z			JA		0-0	21-51-12	D40056J	S/R			D03862			AH	YC051-YD153
2076Z			JA		0-0	21-51-12	D40056J	S/R			GD05122	ST..	GW	*	YD154-YL999, YR301-YR328
2077B	20	HF	JB		17-5	21-51-12	D40056J	5			D03862	4			YC051-YL999, YR301-YR328
2077R	20	HF	JB		0-0	21-51-12	D40056J	6			D03862	12			YC051-YL999, YR301-YR328
2077Z			JB		0-0	21-51-12	D40056J	S/R			D03862			AH	YC051-YD153
2077Z			JB		0-0	21-51-12	D40056J	S/R			GD05122	ST..	GW	*	YD154-YL999, YR301-YR328
2078B	20	HF	JC		17-5	21-51-12	D40056J	3			D03862	1			YC051-YL999, YR301-YR328
2078R	20	HF	JC		0-0	21-51-12	D40056J	4			D03862	2			YC051-YL999, YR301-YR328
2078Z			JC		0-0	21-51-12	D40056J	S/R			D03862			AH	YC051-YD153
2078Z			JC		0-0	21-51-12	D40056J	S/R			GD05122	ST..	GW	*	YD154-YL999, YR301-YR328
2079B	20	HF	JD		8-3	21-51-12	D40056J	7			D03866	1			YC051-YL999, YR301-YR328
2079R	20	HF	JD		0-0	21-51-12	D40056J	8			D03866	2			YC051-YL999, YR301-YR328
2079Z			JD		0-0	21-51-12	D40056J	S/R			GD05130	ST..	GW	*2	YC051-YL999, YR301-YR328
2080B	20	HF	JE		8-3	21-51-13	D40056J	20			D03866	3			YC051-YL999, YR301-YR328
2080R	20	HF	JE		0-0	21-51-13	D40056J	21			D03866	4			YC051-YL999, YR301-YR328
2080Z			JE		0-0	21-51-13	D40056J	S/R			GD05130	ST..	GW	*2	YC051-YL999, YR301-YR328
2081B	20	HF	JF		14-5	21-51-13	D40056J	22			D03864	3			YC051-YD157

WIRE LIST
D280A108

91-21-11
Section W5100
Page 13
Nov 12/2012



WIRE LIST

91-21-11

Section W5100

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W5103	286A5103				HF-1 E8-1 TO E3-3 (continued)											
0003	22		PA		111-3	23-11-11	D40113P	A05			D43359P	A05			YL951-YL999, YR301-YR328	
0003	22		PA		91-10	23-11-11	D40113P	A05			D43359P	A05			YN231-YN501	
0004	24		PK		17-7	23-12-41	D40075P	B05			D43359P	B05			YD158-YD170	
0004	24		B6		111-3	23-12-41	D40113P	B05			D43359P	B05			YL951-YL999, YR301-YR328	
0004	24		PK		91-10	23-12-41	D40113P	B05			D43359P	B05			YN231-YN501	
2501B	24		Y2	AA	17-7	23-12-41	D40075P	B01			D43359P	B01			YD158-YD170	
2501B	24		Y2	AA	111-3	23-12-41	D40113P	B01			D43359P	B01			YL951-YL999, YR301-YR328	
2501B	24		Y2	AA	91-10	23-12-41	D40113P	B01			D43359P	B01			YN231-YN501	
2501R	24		Y2	AA	0-0	23-12-41	D40075P	A01			D43359P	A01			YD158-YD170	
2501R	24		Y2	AA	0-0	23-12-41	D40113P	A01			D43359P	A01			YL951-YR328	
2501Z				AA	0-0	23-12-41	D40075P	PERG	1F		D43359P	PERG	1F		YD158-YD170	
2501Z				AA	0-0	23-12-41	D40113P	PERG	1F		D43359P	PERG	1F		YL951-YR328	
2502B	24		Y2	AB	17-7	23-12-41	D40075P	B02			D43359P	B02			YD158-YD170	
2502B	24		Y2	AB	111-3	23-12-41	D40113P	B02			D43359P	B02			YL951-YL999, YR301-YR328	
2502B	24		Y2	AB	91-10	23-12-41	D40113P	B02			D43359P	B02			YN231-YN501	
2502R	24		Y2	AB	0-0	23-12-41	D40075P	A02			D43359P	A02			YD158-YD170	
2502R	24		Y2	AB	0-0	23-12-41	D40113P	A02			D43359P	A02			YL951-YR328	
2502Z				AB	0-0	23-12-41	D40075P	PERG	1F		D43359P	PERG	1F		YD158-YD170	
2502Z				AB	0-0	23-12-41	D40113P	PERG	1F		D43359P	PERG	1F		YL951-YR328	
2503B	24		Y2	AC	17-7	23-11-11	D40075P	B03			D43359P	B03			YD158-YD170	
2503B	24		Y2	AC	111-3	23-11-11	D40113P	B03			D43359P	B03			YL951-YL999, YR301-YR328	
2503B	24		Y2	AC	91-10	23-11-11	D40113P	B03			D43359P	B03			YN231-YN501	
2503R	24		Y2	AC	0-0	23-11-11	D40075P	A03			D43359P	A03			YD158-YD170	
2503R	24		Y2	AC	0-0	23-11-11	D40113P	A03			D43359P	A03			YL951-YR328	
2503Z				AC	0-0	23-11-11	D40075P	PERG	1F		D43359P	PERG	1F		YD158-YD170	
2503Z				AC	0-0	23-11-11	D40113P	PERG	1F		D43359P	PERG	1F		YL951-YR328	
2504B	24		Y2	AD	111-3	SPARE	D40113P	B06			D43359P	B06			YL951-YL999	
2504B	24		Y2	AD	91-10	SPARE	D40113P	B06			D43359P	B06			YN231-YN501	
2504R	24		Y2	AD	0-0	SPARE	D40113P	A06			D43359P	A06			YL951-YN501	
2504Z				AD	0-0	SPARE	D40113P	PERG	1F		D43359P	PERG	1F		YL951-YN501	
2505B	24		Y2	AE	111-3	SPARE	D40113P	B07			D43359P	B07			YL951-YL999, YR301-YR328	
2505B	24		Y2	AE	91-10	SPARE	D40113P	B07			D43359P	B07			YN231-YN501	
2505R	24		Y2	AE	0-0	SPARE	D40113P	A07			D43359P	A07			YL951-YR328	

WIRE LIST

D280A108

91-21-11

Section W5100

Page 15

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5103	286A5103				HF-1 E8-1 TO E3-3 (continued)										
2505Z				AE	0-0	SPARE	D40113P	PERG	1F		D43359P	PERG	1F		YL951-YR328
2506B	24	Y2		AD	17-7	SPARE	D40075P	B07			D43359P	B08			YD158-YD170
2506R	24	Y2		AD	0-0	SPARE	D40075P	A07			D43359P	A08			YD158-YD170
2506Z				AD	0-0	SPARE	D40075P	PERG	1F		D43359P	PERG	1F		YD158-YD170
2507B	24	Y2		AG	111-3	SPARE	D40113P	B09			D43359P	B09			YL951-YL999, YR301-YR328
2507B	24	Y2		AG	91-10	SPARE	D40113P	B09			D43359P	B09			YN231-YN501
2507R	24	Y2		AG	0-0	SPARE	D40113P	A09			D43359P	A09			YL951-YR328
2507Z				AG	0-0	SPARE	D40113P	PERG	1F		D43359P	PERG	1F		YL951-YR328
2508B	24	Y2		AH	111-3	SPARE	D40113P	B10			D43359P	B10			YL951-YL999
2508B	24	Y2		AH	91-10	SPARE	D40113P	B10			D43359P	B10			YN231-YN501
2508B	24	Y2		AH	111-3	SPARE	D40113P	B10			D43359P	B08			YR301-YR328
2508R	24	Y2		AH	0-0	SPARE	D40113P	A10			D43359P	A10			YL951-YN501
2508R	24	Y2		AH	0-0	SPARE	D40113P	A10			D43359P	A08			YR301-YR328
2508Z				AH	0-0	SPARE	D40113P	PERG	1F		D43359P	PERG	1F		YL951-YR328
2509B	24	Y2		AI	111-3	SPARE	D40113P	B08			D43359P	B08			YL951-YL999
2509B	24	Y2		AI	91-10	SPARE	D43359P	B08			D40113P	B08			YN231-YN501
2509R	24	Y2		AI	0-0	SPARE	D40113P	A08			D43359P	A08			YL951-YL999
2509R	24	Y2		AI	0-0	SPARE	D43359P	A08			D40113P	A08			YN231-YN501
2509Z				AI	0-0	SPARE	D40113P	PERG	1F		D43359P	PERG	1F		YL951-YL999
2509Z				AI	0-0	SPARE	D43359P	PERG	1F		D40113P	PERG	1F		YN231-YN501
2510B	24	Y2		AE	17-7	23-11-16	D40075P	A14			D43359P	B10			YD158-YD170
2510B	24	Y2		AJ	111-3	SPARE	D40113P	B08			D43359P	B10			YR301-YR328
2510R	24	Y2		AE	0-0	23-11-16	D40075P	A13			D43359P	A10			YD158-YD170
2510R	24	Y2		AJ	0-0	SPARE	D40113P	A08			D43359P	A10			YR301-YR328
2510Z				AE	0-0	23-11-16	D40075P	PERG	1F		D43359P	PERG	1F		YD158-YD170
2510Z				AJ	0-0	SPARE	D40113P	PERG	1F		D43359P	PERG	1F		YR301-YR328
2533B	24	Y2		AW	17-7	23-27-36	D40075P	B08			D43359P	B06			YD158-YD170
2533R	24	Y2		AW	0-0	23-27-36	D40075P	A08			D43359P	A06			YD158-YD170
2533Z				AW	0-0	23-27-36	D40075P	PERG	1F		D43359P	PERG	1F		YD158-YD170
2534B	24	Y2		AX	17-7	23-27-36	D40075P	B09			D43359P	B07			YD158-YD170
2534R	24	Y2		AX	0-0	23-27-36	D40075P	A09			D43359P	A07			YD158-YD170
2534Z				AX	0-0	23-27-36	D40075P	PERG	1F		D43359P	PERG	1F		YD158-YD170
2559B	24	Y2		AY	17-7	SPARE	D40075P	B15			D43359P	B09			YD158-YD170
2559R	24	Y2		AY	0-0	SPARE	D40075P	A15			D43359P	A09			YD158-YD170
2559Z				AY	0-0	SPARE	D40075P	PERG	1F		D43359P	PERG	1F		YD158-YD170
W5104	286A5104				E/E BAY TO L AC PACK (STA 536L) DISC. (LA2)										
0301	24	PK			43-5	21-51-12	D40244P	B07			D40056P		1		YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5100

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description		From				To					
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5104	286A5104			E/E BAY TO L AC PACK (STA 536L) DISC. (LA2) (continued)											
0301	24		PK		43-11	21-51-12	D40244P	B07			D40056P	1			YC056-YL999, YR301-YR323, YR325-YR328
0302	24		PK		43-5	21-51-12	D40244P	B08			D40056P	2			YC051-YC055
0302	24		PK		43-11	21-51-12	D40244P	B08			D40056P	2			YC056-YL999, YR301-YR323, YR325-YR328
0303	24		PK		43-5	21-51-12	D40244P	B09			D40056P	3			YC051-YC055
0303	24		PK		43-11	21-51-12	D40244P	B09			D40056P	3			YC056-YL999, YR301-YR323, YR325-YR328
0304	24		PK		43-5	21-51-12	D40244P	B10			D40056P	4			YC051-YC055
0304	24		PK		43-11	21-51-12	D40244P	B10			D40056P	4			YC056-YL999, YR301-YR323, YR325-YR328
0305	24		PK		42-1	21-51-12	D41800P	A01			D40056P	5			YC051-YC055
0305	24		PK		42-0	21-51-12	D41800P	A01			D40056P	5			YC056-YL999, YR301-YR323, YR325-YR328
0306	24		PK		42-1	21-51-12	D41800P	A02			D40056P	6			YC051-YC055
0306	24		PK		42-0	21-51-12	D41800P	A02			D40056P	6			YC056-YL999, YR301-YR323, YR325-YR328
0307	24		PK		42-1	21-51-12	D41800P	A03			D40056P	7			YC051-YC055
0307	24		PK		42-0	21-51-12	D41800P	A03			D40056P	7			YC056-YL999, YR301-YR323, YR325-YR328
0308	24		PK		42-1	21-51-12	D41800P	A04			D40056P	8			YC051-YC055
0308	24		PK		42-0	21-51-12	D41800P	A04			D40056P	8			YC056-YL999, YR301-YR323, YR325-YR328
0309	24		PK		43-5	21-61-51	D40244P	A08			D40056P	30			YC051-YC055
0309	24		PK		43-11	21-61-51	D40244P	A08			D40056P	30			YC056-YL999, YR301-YR323, YR325-YR328
0310	22		PA		42-5	21-25-11	D40244P	B04			D03856	6			YC051-YC055
0310	22		PA		42-11	21-25-11	D40244P	B04			D03856	6			YC056-YL999, YR301-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W5100

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W5104	286A5104				E/E BAY TO L AC PACK (STA 536L) DISC. (LA2) (continued)											
0311	24		PK		42-1		21-51-13	D41800P	A07			D40056P	20			YC051-YC055
0311	24		PK		42-0		21-51-13	D41800P	A07			D40056P	20			YC056-YL999, YR301-YR323, YR325-YR328
0312	24		PK		42-1		21-51-13	D41800P	A08			D40056P	21			YC051-YC055
0312	24		PK		42-0		21-51-13	D41800P	A08			D40056P	21			YC056-YL999, YR301-YR323, YR325-YR328
0313	24		PK		42-1		21-51-13	D41800P	A09			D40056P	22			YC051-YC055
0313	24		PK		42-0		21-51-13	D41800P	A09			D40056P	22			YC056-YL999, YR301-YR323, YR325-YR328
0314	24		PK		42-1		21-51-13	D41800P	A10			D40056P	23			YC051-YC055
0314	24		PK		42-0		21-51-13	D41800P	A10			D40056P	23			YC056-YL999, YR301-YR323, YR325-YR328
0315	24		PK		42-1		21-51-14	D41800P	B01			D40056P	9			YC051-YC055
0315	24		PK		42-0		21-51-14	D41800P	B01			D40056P	9			YC056-YL999, YR301-YR323, YR325-YR328
0316	24		PK		42-1		21-51-14	D41800P	B02			D40056P	14			YC051-YC055
0316	24		PK		42-0		21-51-14	D41800P	B02			D40056P	14			YC056-YL999, YR301-YR323, YR325-YR328
0317	24		PK		39-10		21-51-14	D40244P	A01			D00966	10			YC051-YC055
0317	24		PK		40-4		21-51-14	D40244P	A01			D00966	10			YC056-YL999, YR301-YR323, YR325-YR328
0324	14		PA		41-10		21-25-11	D41836P		1		D03856	4			YC051-YC055
0324	14		PA		41-9		21-25-11	D41836P		1		D03856	4			YC056-YL999, YR301-YR323, YR325-YR328
0325	14		PA		41-10		21-25-11	D41836P		2		D03856	3			YC051-YC055
0325	14		PA		41-9		21-25-11	D41836P		2		D03856	3			YC056-YL999, YR301-YR323, YR325-YR328
0326	14		PA		41-10		21-25-11	D41836P		3		D03856	2			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5100

Page 18

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Fam	Description FT-IN	Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W5104	286A5104				E/E BAY TO L AC PACK (STA 536L) DISC. (LA2) (continued)										
0326	14	PA			41-9	21-25-11	D41836P	3			D03856	2			YC056-YL999, YR301-YR323, YR325-YR328
0327	14	PA			3-0	21-25-11	D03856	7			GD03258	ST..	E		YC051-YL999, YR301-YR323, YR325-YR328
0328	20	PA			7-11	21-25-11	D03856	5			GD00068	DC..	1		YC051-YL999, YR301-YR323, YR325-YR328
1201	20	X1	DA		41-0	33-44-11	D40246P	A07			D40056P	15			YC051-YC055
1201	20	X1	DA		41-3	33-44-11	D40246P	A07			D40056P	15			YC056-YL999, YR301-YR323, YR325-YR328
1201	20	X1	DA		30-11	33-44-11	D40246P	A07			D40056P	15			YN231-YN236, YN501
1201Z			DA		0-0	33-44-11	D40246P	PERG	1F		D40056P	S/R			YC051-YN236, YN501-YR323, YR325-YR328
2001B	20	PB	GA		37-9	21-51-12	D41800P	A05			D03868	1			YC051-YC055
2001B	20	PB	GA		37-8	21-51-12	D41800P	A05			D03868	1			YC056-YL999, YR301-YR323, YR325-YR328
2001R	20	PB	GA		0-0	21-51-12	D41800P	A06			D03868	2			YC051-YL999, YR301-YR323, YR325-YR328
5501	24	PK			33-7	21-51-14	D40244P	A01			D40056P	1			YN231-YN236, YN501
5502	24	PK			1-0	21-51-14	D40244P	A02			SM00001		9		YC051-YC055, YN231-YN236, YN501
5502	24	PK			0-7	21-51-14	D40244P	A02			SM00001		9		YC056-YL999, YR301-YR323, YR325-YR328
5503	24	PK			39-10	21-51-14	D40244P	A03			D00966	1			YC051-YC055
5503	24	PK			40-4	21-51-14	D40244P	A03			D00966	1			YC056-YL999, YR301-YR323, YR325-YR328
5503	24	PK			30-6	21-51-14	D40244P	A03			D00966	1			YN231-YN236, YN501
5504	24	PK			39-10	21-51-14	D40244P	A04			D00966	7			YC051-YC055
5504	24	PK			40-4	21-51-14	D40244P	A04			D00966	7			YC056-YL999, YR301-YR323, YR325-YR328

WIRE LIST
D280A108

91-21-11
Section W5100
Page 19
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5104		286A5104			E/E BAY TO L AC PACK (STA 536L) DISC. (LA2) (continued)										
5504	24	PK			30-6	21-51-14	D40244P	A04			D00966	7			YN231-YN236, YN501
5505	24	PK			33-7	21-51-16	D40244P	B04			D40056P	14			YN231-YN236, YN501
5506	24	PK			33-7	21-61-21	D40244P	A05			D40056P	7			YN231-YN236, YN501
5507	24	PK			33-7	21-61-21	D40244P	A06			D40056P	6			YN231-YN236, YN501
5508	24	PK			33-7	21-61-21	D40244P	A07			D40056P	9			YN231-YN236, YN501
5509	24	PK			33-7	21-61-21	D40244P	A08			D40056P	8			YN231-YN236, YN501
5515	24	PK			41-0	36-21-11	D40246P	A03			D40056P	11			YC051-YC055
5515	24	PK			41-3	36-21-11	D40246P	A03			D40056P	11			YC056-YL999, YR301-YR323, YR325-YR328
5515	24	PK			30-11	36-21-11	D40246P	A03			D40056P	11			YN231-YN236, YN501
5516	24	PK			41-0	36-21-11	D40246P	A04			D40056P	12			YC051-YC055
5516	24	PK			41-3	36-21-11	D40246P	A04			D40056P	12			YC056-YL999, YR301-YR323, YR325-YR328
5516	24	PK			30-11	36-21-11	D40246P	A04			D40056P	12			YN231-YN236, YN501
5517	24	PK			41-0	36-21-11	D40246P	A05			D40056P	13			YC051-YC055
5517	24	PK			41-3	36-21-11	D40246P	A05			D40056P	13			YC056-YL999, YR301-YR323, YR325-YR328
5517	24	PK			30-11	36-21-11	D40246P	A05			D40056P	13			YN231-YN236, YN501
5520	20	PA			43-5	SPARE	D40056P	18			D40244P	B05			YC051-YC055
5520	20	PA			43-11	SPARE	D40056P	18			D40244P	B05			YC056-YL999, YR301-YR323, YR325-YR328
5520	20	PA			33-7	SPARE	D40056P	18			D40244P	B05			YN231-YN236, YN501
5521	20	PA			43-5	SPARE	D40056P	19			D40244P	B06			YC051-YC055
5521	20	PA			43-11	SPARE	D40056P	19			D40244P	B06			YC056-YL999, YR301-YR323, YR325-YR328
5521	20	PA			33-7	SPARE	D40056P	19			D40244P	B06			YN231-YN236, YN501
5522	20	PA			41-0	SPARE	D40056P	16			D40246P	A08			YC051-YC055
5522	20	PA			41-3	SPARE	D40056P	16			D40246P	A08			YC056-YL999, YR301-YR323, YR325-YR328
5522	20	PA			30-11	SPARE	D40056P	16			D40246P	A08			YN231-YN236, YN501
5524	22	PA			39-4	21-51-14	D00966	5			SM00001	9			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5100

Page 20

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY	Description Fam FT-IN Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W5104	286A5104	E/E BAY TO L AC PACK (STA 536L) DISC. (LA2) (continued)									
5524	22 PA	40-4 21-51-14	D00966	5			SM00001		9		YC056-YL999, YR301-YR323, YR325-YR328
5524	22 PA	29-6 21-51-14	D00966	5			SM00001		9		YN231-YN236, YN501
5525	20 PA	3-3 21-51-14	D00966	11			GD00068	AC..	1		YC051-YL999, YR301-YR323, YR325-YR328
5525	20 PA	3-2 21-51-14	D00966	11			GD00068	AC..	1		YN231-YN236, YN501
5526	22 PA	39-4 21-51-14	D00966	6			SM00001		9		YC051-YC055
5526	22 PA	40-4 21-51-14	D00966	6			SM00001		9		YC056-YL999, YR301-YR323, YR325-YR328
5526	22 PA	29-6 21-51-14	D00966	6			SM00001		9		YN231-YN236, YN501
5527	20 PA	3-3 21-51-14	D00966	8			GD00068	DC..	1		YC051-YL999, YR301-YR323, YR325-YR328
5527	20 PA	3-2 21-51-14	D00966	8			GD00068	DC..	1		YN231-YN236, YN501
5528	22 PA	8-4 21-51-14	D00966	10			D40056P		3		YN231-YN236, YN501
5529	22 PA	32-7 21-51-14	SM00001	9			D40056P		2		YN231-YN236, YN501
W5105	286A5105	HF-2 E8-1 TO E3-3									
0001	22 PA	31-3 23-11-26	D40077P	A02			D43361P	A02			YD158-YD170
0001	22 PA	109-6 SPARE	D40115P	A02			D43361P	A02			YL951-YL999, YR301-YR328
0001	22 PA	90-2 SPARE	D40115P	A02			D43361P	A02			YN231-YN501
0002	22 PA	31-3 23-11-21	D40077P	B02			D43361P	B02			YD158-YD170
0002	22 PA	109-6 23-11-21	D40115P	B02			D43361P	B02			YL951-YL999, YR301-YR328
0002	22 PA	90-2 23-11-21	D40115P	B02			D43361P	B02			YN231-YN501
0003	22 PA	31-3 23-11-21	D40077P	A03			D43361P	A03			YD158-YD170
0003	22 PA	109-6 23-11-21	D40115P	A03			D43361P	A03			YL951-YL999, YR301-YR328
0003	22 PA	90-2 23-11-21	D40115P	A03			D43361P	A03			YN231-YN501
0004	24 PK	31-3 23-12-41	D40077P	B03			D43361P	B03			YD158-YD170
0004	24 PK	109-6 23-12-41	D40115P	B03			D43361P	B03			YL951-YL999, YR301-YR328
0004	24 PK	90-2 23-12-41	D40115P	B03			D43361P	B03			YN231-YN501
2501B	24 Y2 AA	31-3 23-11-21	D40077P	B01			D43361P	B01			YD158-YD170

WIRE LIST
D280A108

91-21-11
Section W5100
Page 21
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5105	286A5105			HF-2 E8-1 TO E3-3 (continued)											
2501B	24	Y2	AA		109-6	23-11-21	D40115P	B01			D43361P	B01			YL951-YL999, YR301-YR328
2501B	24	Y2	AA		90-2	23-11-21	D40115P	B01			D43361P	B01			YN231-YN501
2501R	24	Y2	AA		0-0	23-11-21	D40077P	A01			D43361P	A01			YD158-YD170
2501R	24	Y2	AA		0-0	23-11-21	D40115P	A01			D43361P	A01			YL951-YR328
2501Z			AA		0-0	23-11-21	D40077P	PERG	1F		D43361P	PERG	1F		YD158-YD170
2501Z			AA		0-0	23-11-21	D40115P	PERG	1F		D43361P	PERG	1F		YL951-YR328
2502B	24	Y2	AB		109-6	SPARE	D40115P	B05			D43361P	B10			YL951-YL999, YR301-YR328
2502R	24	Y2	AB		0-0	SPARE	D40115P	A05			D43361P	A10			YL951-YL999, YR301-YR328
2502Z			AB		0-0	SPARE	D40115P	PERG	1F		D43361P	PERG	1F		YL951-YL999, YR301-YR328
2503B	24	Y2	AC		109-6	SPARE	D40115P	B04			D43361P	B07			YL951-YL999, YR301-YR328
2503R	24	Y2	AC		0-0	SPARE	D40115P	A04			D43361P	A07			YL951-YL999, YR301-YR328
2503Z			AC		0-0	SPARE	D40115P	PERG	1F		D43361P	PERG	1F		YL951-YL999, YR301-YR328
2504B	24	Y2	AD		109-6	SPARE	D40115P	B06			D43361P	B04			YL951-YL999, YR301-YR328
2504B	24	Y2	AD		90-2	SPARE	D40115P	B06			D43361P	B04			YN231-YN501
2504R	24	Y2	AD		0-0	SPARE	D40115P	A06			D43361P	A04			YL951-YR328
2504Z			AD		0-0	SPARE	D40115P	PERG	1F		D43361P	PERG	1F		YL951-YR328
2505B	24	Y2	AE		109-6	SPARE	D40115P	B07			D43361P	B05			YL951-YL999, YR301-YR328
2505B	24	Y2	AE		90-2	SPARE	D40115P	B07			D43361P	B05			YN231-YN501
2505R	24	Y2	AE		0-0	SPARE	D40115P	A07			D43361P	A05			YL951-YR328
2505Z			AE		0-0	SPARE	D40115P	PERG	1F		D43361P	PERG	1F		YL951-YR328
2507B	24	Y2	AG		109-6	SPARE	D40115P	B08			D43361P	B08			YL951-YL999, YR301-YR328
2507B	24	Y2	AG		90-2	SPARE	D40115P	B08			D43361P	B08			YN231-YN501
2507R	24	Y2	AG		0-0	SPARE	D40115P	A08			D43361P	A08			YL951-YR328
2507Z			AG		0-0	SPARE	D40115P	PERG	1F		D43361P	PERG	1F		YL951-YR328
2508B	24	Y2	AH		109-6	SPARE	D40115P	B09			D43361P	B09			YL951-YL999, YR301-YR328
2508B	24	Y2	AH		90-2	SPARE	D40115P	B09			D43361P	B09			YN231-YN501
2508R	24	Y2	AH		0-0	SPARE	D40115P	A09			D43361P	A09			YL951-YR328
2508Z			AH		0-0	SPARE	D40115P	PERG	1F		D43361P	PERG	1F		YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5100

Page 22

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5105	286A5105				HF-2 E8-1 TO E3-3 (continued)										
2509B	24	Y2	AI		109-6	SPARE	D40115P	B10			D43361P	B06			YL951-YL999, YR301-YR328
2509B	24	Y2	AI		90-2	SPARE	D40115P	B10			D43361P	B06			YN231-YN501
2509R	24	Y2	AI		0-0	SPARE	D40115P	A10			D43361P	A06			YL951-YR328
2509Z			AI		0-0	SPARE	D40115P	PERG	1F		D43361P	PERG	1F		YL951-YR328
2510B	24	Y2	AG		31-3	23-11-26	D40077P	B09			D43361P	B09			YD158-YD170
2510R	24	Y2	AG		0-0	23-11-26	D40077P	A09			D43361P	A09			YD158-YD170
2510Z			AG		0-0	23-11-26	D40077P	PERG	1F		D43361P	PERG	1F		YD158-YD170
2533B	24	Y2	AE		31-3	23-27-36	D40077P	B07			D43361P	B06			YD158-YD170
2533R	24	Y2	AE		0-0	23-27-36	D40077P	A07			D43361P	A06			YD158-YD170
2533Z			AE		0-0	23-27-36	D40077P	PERG	1F		D43361P	PERG	1F		YD158-YD170
2534B	24	Y2	AF		31-3	SPARE	D40077P	B08			D43361P	B07			YD158-YD170
2534R	24	Y2	AF		0-0	SPARE	D40077P	A08			D43361P	A07			YD158-YD170
2534Z			AF		0-0	SPARE	D40077P	PERG	1F		D43361P	PERG	1F		YD158-YD170
2539B	24	Y2	AY		31-3	SPARE	D40077P	B14			D43361P	B10			YD158-YD170
2539R	24	Y2	AY		0-0	SPARE	D40077P	A14			D43361P	A10			YD158-YD170
2539Z			AY		0-0	SPARE	D40077P	PERG	1F		D43361P	PERG	1F		YD158-YD170
W5107	286A5107				VHF-1 & VHF-2, E1-3, E1-5 TO E3-3										
0003	24	PK			25-1	23-12-41	D04123P	10			D43367P	A07			YD158, YL951-YR328
0004	22	PA			25-1	23-12-11	D04123P	11			D43367P	B07			YD158, YL951-YR328
0005	24	PK			25-3	23-12-41	D04125J	8			D43367P	A08			YD158
0005	24	B6			25-1	23-12-41	D04125J	8			D43314P	A07			YL951-YR328
0006	22	CQ			25-3	23-12-21	D04125J	9			D43367P	B08			YD158
0006	22	CQ			25-1	23-12-21	D04125J	9			D43314P	B07			YL951-YR328
2501B	24	Y2	AA		25-1	23-12-41	D04123P	2			D43367P	B01			YD158, YL951-YR328
2501R	24	Y2	AA		0-0	23-12-41	D04123P	1			D43367P	A01			YD158, YL951-YR328
2501Z			AA		0-0	23-12-41	D04123P	3			D43367P	PERG	1F		YD158, YL951-YR328
2502B	24	Y2	AB		25-1	23-12-11	D04123P	5			D43367P	B02			YD158, YL951-YR328
2502R	24	Y2	AB		0-0	23-12-11	D04123P	4			D43367P	A02			YD158, YL951-YR328
2502Z			AB		0-0	23-12-11	D04123P	6			D43367P	PERG	1F		YD158, YL951-YR328
2503B	24	Y2	AC		25-1	23-12-41	D04123P	8			D43367P	B03			YD158, YL951-YR328
2503R	24	Y2	AC		0-0	23-12-41	D04123P	7			D43367P	A03			YD158, YL951-YR328
2503Z			AC		0-0	23-12-41	D04123P	9			D43367P	PERG	1F		YD158, YL951-YR328
2504B	24	Y2	AD		25-3	23-12-41	D04125J	2			D43367P	B04			YD158
2504B	24	Y2	AD		25-1	23-12-41	D04125J	2			D43314P	B01			YL951-YR328
2504R	24	Y2	AD		0-0	23-12-41	D04125J	1			D43367P	A04			YD158
2504R	24	Y2	AD		0-0	23-12-41	D04125J	1			D43314P	A01			YL951-YR328
2504Z			AD		0-0	23-12-41	D04125J	S/R			D43367P	PERG	1F		YD158

WIRE LIST

D280A108

91-21-11

Section W5100

Page 23

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5107	286A5107			VHF-1 & VHF-2, E1-3, E1-5 TO E3-3 (continued)											
2504Z				AD	0-0	23-12-41	D04125J	S/R			D43314P	PERG	1F		YL951-YR328
2505B	24	Y2		AE	25-3	23-12-21	D04125J	4			D43367P	B05			YD158
2505B	24	Y2		AE	25-1	23-12-21	D04125J	4			D43314P	B02			YL951-YR328
2505R	24	Y2		AE	0-0	23-12-21	D04125J	3			D43367P	A05			YD158
2505R	24	Y2		AE	0-0	23-12-21	D04125J	3			D43314P	A02			YL951-YR328
2505Z				AE	0-0	23-12-21	D04125J	S/R			D43367P	PERG	1F		YD158
2505Z				AE	0-0	23-12-21	D04125J	S/R			D43314P	PERG	1F		YL951-YR328
2506B	24	Y2		AF	25-3	23-12-41	D04125J	6			D43367P	B06			YD158
2506B	24	Y2		AF	25-1	23-12-41	D04125J	6			D43314P	B03			YL951-YR328
2506R	24	Y2		AF	0-0	23-12-41	D04125J	5			D43367P	A06			YD158
2506R	24	Y2		AF	0-0	23-12-41	D04125J	5			D43314P	A03			YL951-YR328
2506Z				AF	0-0	23-12-41	D04125J	S/R			D43367P	PERG	1F		YD158
2506Z				AF	0-0	23-12-41	D04125J	S/R			D43314P	PERG	1F		YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5100

Page 24 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5110	286A5110			P91 (AFT DISC) TO E/E BAY											
0101	20	PA			2-9	52-71-11	GD11306	AC..	1		SP01120		9		ALL
0501	22	PA			13-4	24-23-51	D11432		1		D40338P	A01			YC051-YC055
0501	22	PA			13-11	24-23-51	D11432		1		D40338P	A01			YC056-YR328
0502	22	PA			13-4	24-28-41	D40338P	B01			D11432	5			YC051-YC055
0502	22	PA			13-11	24-28-41	D40338P	B01			D11432	5			YC056-YR328
0503	22	PA			13-4	24-28-41	D40338P	A02			D11432	4			YC051-YC055
0503	22	PA			13-11	24-28-41	D40338P	A02			D11432	4			YC056-YR328
0505	24	PK			9-1	24-28-41	D40338P	A03			D40340P	A05			YC051-YC055
0505	24	PK			9-7	24-28-41	D40338P	A03			D40340P	A05			YC056-YR328
0506	20	PA			9-1	24-41-11	D40340P	H			D40338P	J			YC051-YC055
0506	20	PA			9-7	24-41-11	D40340P	H			D40338P	J			YC056-YR328
0507	22	PA			13-4	24-23-11	D11432		29		D40338P	B03			YC051-YC055
0507	22	PA			13-11	24-23-11	D11432		29		D40338P	B03			YC056-YR328
0508	22	PA			13-4	24-23-11	D11432		15		D40338P	A04			YC051-YC055
0508	22	PA			13-11	24-23-11	D11432		15		D40338P	A04			YC056-YR328
0509	22	PA			5-5	24-22-11	D11432		50		D40340P	A04			ALL
0510	20	CQ			2-8	29-11-12	D11432		3		SP00010		S		ALL
0513	22	PA			5-5	24-22-11	D11432		13		D40340P	B03			ALL
0516	20	PA			9-1	SPARE	D40338P	A10			D40340P	B01			YC051-YC055
0516	20	PA			9-7	SPARE	D40338P	A10			D40340P	B01			YC056-YR328
0519	22	PA			13-4	24-22-21	D11432		14		D40338P	B04			YC051-YC055
0519	22	PA			13-11	24-22-21	D11432		14		D40338P	B04			YC056-YR328
0521	24	B6			5-1	24-31-12	D10342		3		D10330	3			YC051-YD158
0521	24	B6			6-1	24-31-12	D10342		3		D10330	3			YD160-YR328
0522	22	PA			9-1	24-22-11	D40340P	A03			D40338P	B05			YC051-YC055
0522	22	PA			9-7	24-22-11	D40340P	A03			D40338P	B05			YC056-YR328
0523	24	B6			5-1	24-31-12	D10342		1		D10330	1			YC051-YD158
0523	24	B6			6-1	24-31-12	D10342		1		D10330	1			YD160-YR328
0524	22	PA			9-1	24-22-11	D40340P	B02			D40338P	A05			YC051-YC055
0524	22	PA			9-7	24-22-11	D40340P	B02			D40338P	A05			YC056-YR328
0525	24	B6			5-1	24-31-12	D10342		12		D10330	12			YC051-YD158
0525	24	B6			6-1	24-31-12	D10342		12		D10330	12			YD160-YR328
0526	24	B6			5-1	24-31-12	D10342		11		D10330	11			YC051-YD158
0526	24	B6			6-1	24-31-12	D10342		11		D10330	11			YD160-YR328
0527	24	B6			8-6	24-31-12	D10342		9		TB5801X	A003	1A		YC051-YC055
0527	24	B6			9-0	24-31-12	D10342		9		TB5801X	A003	1A		YC056-YR328
0529	24	B6			4-9	24-31-12	TB5801X	B001	1A		C01212	3	1A		ALL
0530	24	B6			8-6	24-31-12	D10342		8		TB5801X	B002	1A		YC051-YC055
0530	24	B6			9-0	24-31-12	D10342		8		TB5801X	B002	1A		YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W5110

Page 1

Nov 12/2012

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity	
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W5110	286A5110			P91 (AFT DISC) TO E/E BAY (continued)											
0531	20		CQ		4-7	24-31-12	C01212	5A	1A		GD03200	ST..	1A		YC051-YD158
0531	20		CQ		3-0	24-31-12	C01212	5A	1A		GD03200	ST..	1A		YD160-YR328
0532	22		PA		13-4	24-22-11	D11432	32			D40338P	A07			YC051-YC055
0532	22		PA		13-11	24-22-11	D11432	32			D40338P	A07			YC056-YR328
0533	22		PA		5-5	24-22-11	D11432	33			D40340P	B04			ALL
0534	20		PA		4-2	38-41-13	D11432	41			D40260P	A03			ALL
0535	20		PA		4-2	38-41-13	D11432	40			D40260P	B03			ALL
0536	20		PA		4-2	38-41-13	D11432	39			D40260P	A04			ALL
0537	20		PA		4-2	38-41-13	D11432	19			D40260P	B04			ALL
0538	24		B6		0-7	24-31-12	D10342	5			D10342	6			ALL
0539	20		CQ		6-11	24-31-12	D10342	2			GD03200	ST..	1A		YC051-YD158
0539	20		CQ		7-5	24-31-12	D10342	2			GD03200	ST..	1A		YD160-YR328
2419B	20		PB	OT	28-5	52-71-11	D40338P	B06			SP01122		9		YC051-YC055
2419B	20		PB	OT	29-5	52-71-11	D40338P	B06			SP01122		9		YC056-YR328
2419R	20		PB	OT	0-0	52-71-11	D40338P	A06			SP01118		9		ALL
3201B	20		PC	YA	5-5	24-22-11	D11432	56			D40340P	B05			ALL
3201R	20		PC	YA	0-0	24-22-11	D11432	55			D40340P	A06			ALL
3201Y	20		PC	YA	0-0	24-22-11	D11432	53			D40340P	B06			ALL
3202B	20		PC	YB	5-5	24-23-11	D11432	48			D40340P	B07			ALL
3202R	20		PC	YB	0-0	24-23-11	D11432	49			D40340P	A07			ALL
3202Y	20		PC	YB	0-0	24-23-11	D11432	51			D40340P	A08			ALL
3203B	20		PC	YC	21-7	24-31-12	D10342	7			D11432	44			YC051-YC055
3203B	20		PC	YC	22-4	24-31-12	D11432	44			D10342	7			YC056-YD158
3203B	20		PC	YC	22-1	24-31-12	D11432	44			D10342	7			YD160-YR328
3203R	20		PC	YC	0-0	24-31-12	D10342	10			D11432	43			YC051-YC055
3203R	20		PC	YC	0-0	24-31-12	D11432	43			D10342	10			YC056-YR328
3203Y	20		PC	YC	0-0	24-31-12	D10342	4			D11432	24			YC051-YC055
3203Y	20		PC	YC	0-0	24-31-12	D11432	24			D10342	4			YC056-YR328
4101B	22		PD	N6	5-5	24-24-11	D40340P	A09			D11432	47			ALL
4101G	22		PD	N6	0-0	24-24-11	D40340P	B09			D11432	27			ALL
4101R	22		PD	N6	0-0	24-24-11	D40340P	B08			D11432	46			ALL
4101Y	22		PD	N6	0-0	24-24-11	D40340P	A10			D11432	26			ALL
5501	22		PA		5-5	21-27-21	D11432	8			D40340P	A01			YC051-YC059, YC065-YR328 YC060-YC064
5502	22		PA		5-5	21-27-21	SP00469		9		D11432	8			
A-A					0-0	52-71-11	S00199	RED			SP01118		9		ALL
A-B					0-0	52-71-11	S00199	BLU			SP01122		9		ALL
A-C					0-0	52-71-11	S00199	YEL			SP01120		9		ALL

WIRE LIST

D280A108

91-21-11

Section W5110

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5111	286A5111			EE INTER-RACK - LEFT (E1-X TO E3-X)											
0001	22		CQ		11-1	22-11-18	D45115J		1		D45113P	A01			ALL
0002	22		PA		11-1	34-51-11	D45115J		2		D45113P	B01			ALL
0003	22		PA		21-9	27-32-11	D45113P		A02		D45117P	A01			YC051-YC055
0003	22		PA		22-8	27-32-11	D45113P		A02		D45117P	A01			YC056-YR328
0004	24		PK		21-1	34-45-11	D45111P		A01		D45113P	B02			YC051-YC055
0004	24		PK		22-0	34-45-11	D45111P		A01		D45113P	B02			YC056-YR328
0005	22		PA		2-5	SPARE	D45111P		B01		D45117P	B03			YC051-YC055
0005	22		PA		2-4	SPARE	D45111P		B01		D45117P	B03			YC056-YR328
0006	22		PA		21-9	27-32-11	D45113P		A20		D45117P	A20			YC051-YC055
0006	22		PA		22-8	27-32-11	D45113P		A20		D45117P	A20			YC056-YR328
0007	22		CQ		21-9	27-83-11	D45113P		B19		D45117P	B20			YC051-YC055
0007	22		CQ		22-8	27-83-11	D45113P		B19		D45117P	B20			YC056-YR328
0008	24		B6		21-9	22-11-14	D45113P		A03		D45117P	A04			YC051-YC055
0008	24		B6		22-8	22-11-14	D45113P		A03		D45117P	A04			YC056-YR328
0009	22		PA		21-9	27-32-11	D45113P		B20		D45117P	B04			YC051-YC055
0009	22		PA		22-8	27-32-11	D45113P		B20		D45117P	B04			YC056-YR328
0013	22		PA		11-1	SPARE	D45115J		4		D45113P	A19			YC051-YC058
0013	24		PK		11-8	22-11-53	D45115J		4		D41153P	A02			YC059-YR328
0015	22		PA		2-5	29-32-11	D45131P		A02		D45137P	A01			YC051-YC055
0015	22		PA		2-4	29-32-11	D45131P		A02		D45137P	A01			YC056-YR328
0016	22		PA		2-5	29-32-11	D45131P		B02		D45137P	B01			YC051-YC055
0016	22		PA		2-4	29-32-11	D45131P		B02		D45137P	B01			YC056-YR328
0017	22		PA		21-3	34-49-11	D45133P		A01		D45131P	A04			YC051-YC052
0018	22		PA		21-3	34-49-11	D45133P		B01		D45131P	B04			YC051-YC052
0019	22		PA		11-3	SPARE	D45115J		6		D45133P	A02			YC051-YC058
0019	24		PK		11-8	22-11-53	D45115J		6		D41153P	B02			YC059-YR328
0020	22		PA		11-3	SPARE	D45115J		7		D45133P	B02			YC051-YC058
0020	24		PK		11-8	22-11-53	D45115J		7		D41153P	A03			YC059-YR328
0021	22		PA		11-3	SPARE	D45115J		8		D45133P	A03			YC051-YC058
0021	24		PK		11-8	22-11-53	D45115J		8		D41153P	B03			YC059-YR328
0024	22		PA		28-9	SPARE	D45115J		9		D45111P	B02			YC051-YC055
0024	22		PA		29-8	SPARE	D45115J		9		D45111P	B02			YC056-YR328
0025	22		CQ		28-9	22-11-18	D45115J		10		D45111P	A02			YC051-YC055
0025	22		CQ		29-8	22-11-18	D45115J		10		D45111P	A02			YC056-YR328
0026	22		CQ		29-5	22-11-18	D45115J		53		D45137P	B03			YC051-YC055
0026	22		CQ		30-3	22-11-18	D45115J		53		D45137P	B03			YC056-YR328
0027	20		PA		21-9	22-23-11	D45113P		B03		D45117P	B01			YC051-YC055
0027	20		PA		22-8	22-23-11	D45113P		B03		D45117P	B01			YC056-YR328
0028	22		PA		11-1	23-51-51	D45113P		B17		D45115J	55			ALL

WIRE LIST

D280A108

91-21-11

Section W5110

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5111	286A5111			EE INTER-RACK - LEFT (E1-X TO E3-X) (continued)											
0030	20		CQ		2-9	SPARE	D45157P	A05			D43307P	B16			YC051-YC053
0030	20		CQ		2-8	SPARE	D45157P	A05			D43307P	B16			YD158-YR328
0031	20		CQ		2-9	SPARE	D45157P	B05			D43307P	A17			YC051-YC053
0031	20		CQ		2-8	SPARE	D45157P	B05			D43307P	A17			YD158-YR328
0032	22		PA		2-9	SPARE	D45157P	A06			D43307P	B17			YC051-YC055
0032	22		PA		2-8	SPARE	D45157P	A06			D43307P	B17			YC056-YR328
0033	24		B6		2-9	31-31-17	D45157P	B06			D43307P	A16			YC051-YC055
0033	24		B6		2-8	31-31-17	D45157P	B06			D43307P	A16			YC056-YR328
0034	22		PA		2-9	23-27-12	D45157P	A01			D43307P	A12			YC051-YC055
0034	22		PA		2-8	23-27-12	D45157P	A01			D43307P	A12			YC056-YD157
0034	22		PA		2-8	23-27-38	D45157P	A01			D43307P	A12			YD158-YR328
0035	22		PA		2-9	23-27-12	D45157P	B01			D43307P	B12			YC051-YC055
0035	22		PA		2-8	23-27-12	D45157P	B01			D43307P	B12			YC056-YD157
0035	22		PA		2-8	23-27-38	D45157P	B01			D43307P	B12			YD158-YR328
0036	22		PA		2-9	23-27-12	D45157P	A02			D43307P	A13			YC051-YC055
0036	22		PA		2-8	23-27-12	D45157P	A02			D43307P	A13			YC056-YD157
0036	22		PA		2-8	23-27-38	D45157P	A02			D43307P	A13			YD158-YR328
0037	22		PA		2-9	23-27-12	D45157P	B02			D43307P	B13			YC051-YC055
0037	22		PA		2-8	23-27-12	D45157P	B02			D43307P	B13			YC056-YD157
0037	22		PA		2-8	23-27-38	D45157P	B02			D43307P	B13			YD158-YR328
0038	22		PA		2-9	SPARE	D45157P	A03			D43307P	A14			YC051-YC055
0038	22		PA		2-8	SPARE	D45157P	A03			D43307P	A14			YC056-YD170
0039	22		PA		2-9	SPARE	D45157P	B03			D43307P	B14			YC051-YC055
0039	22		PA		2-8	SPARE	D45157P	B03			D43307P	B14			YC056-YD170
0040	22		PA		2-9	23-27-14	D45157P	A04			D43307P	A15			YC051-YC055
0040	22		PA		2-8	23-27-14	D45157P	A04			D43307P	A15			YC056-YD157
0040	22		PA		2-8	23-27-38	D45157P	A04			D43307P	A15			YD158-YR328
0041	22		PA		2-9	23-27-14	D45157P	B04			D43307P	B15			YC051-YC055
0041	22		PA		2-8	23-27-14	D45157P	B04			D43307P	B15			YC056-YD157
0041	22		PA		2-8	23-27-38	D45157P	B04			D43307P	B15			YD158-YR328
0042	24		PK		32-9	23-27-11	D45211J	A01			D43321P	A14			YC051-YC055
0042	24		PK		33-7	23-27-11	D45211J	A01			D43321P	A14			YC056-YD157
0042	24		PK		33-7	23-27-39	D45211J	A01			D43321P	A14			YD158-YR328
0043	22		PA		21-1	34-49-11	D45113P	B16			D45131P	A01			YC051-YC052
0047	22		PA		21-9	22-23-11	D45113P	A17			D45117P	A02			YC051-YC055
0047	22		PA		22-8	22-23-11	D45113P	A17			D45117P	A02			YC056-YR328
0081	20		PA		33-7	23-32-21	D45211J	B01			D43321P	B14			YL951-YL967, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W5110

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From				To						
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5111	286A5111			EE INTER-RACK - LEFT (E1-X TO E3-X) (continued)											
0085	24		PK		2-8	23-27-31	D45157P	A03			D43307P	A14			YL951-YL954, YN231-YN235
0086	24		PK		2-8	23-27-31	D45157P	A07			D43307P	B14			YL951-YL954, YN231-YN235
1001	22		X1	CC	2-5	31-62-14	D45131P	A05			D45137P	A19			YC051-YC055
1001	22		X1	CC	2-4	31-62-14	D45131P	A05			D45137P	A19			YC056-YR328
1001Z				CC	0-0	31-62-14	D45131P	PERG	1F		D45137P	PERG	1F		ALL
2001B	24		Y2	AA	11-1	34-31-11	D45115J	12			D45113P	B05			ALL
2001R	24		Y2	AA	0-0	34-31-11	D45115J	11			D45113P	A05			ALL
2001Z				AA	0-0	34-31-11	D45115J	S/R			D45113P	PERG	1F		ALL
2002B	24		Y2	AB	11-1	34-31-11	D45115J	14			D45113P	B06			ALL
2002R	24		Y2	AB	0-0	34-31-11	D45115J	13			D45113P	A06			ALL
2002Z				AB	0-0	34-31-11	D45115J	S/R			D45113P	PERG	1F		ALL
2003B	24		Y2	AC	29-5	34-31-11	D45115J	16			D45117P	B06			YC051-YC055
2003B	24		Y2	AC	30-4	34-31-11	D45115J	16			D45117P	B06			YC056-YR328
2003R	24		Y2	AC	0-0	34-31-11	D45115J	15			D45117P	A06			ALL
2003Z				AC	0-0	34-31-11	D45115J	S/R			D45117P	PERG	1F		ALL
2004B	24		Y2	AD	28-9	34-31-11	D45111P	B03			D45115J	18			YC051-YC055
2004B	24		Y2	AD	29-8	34-31-11	D45111P	B03			D45115J	18			YC056-YR328
2004R	24		Y2	AD	0-0	34-31-11	D45111P	A03			D45115J	17			ALL
2004Z				AD	0-0	34-31-11	D45111P	PERG	1F		D45115J	S/R			ALL
2005B	24		Y2	AE	28-9	SPARE	D45111P	B04			D45115J	20			YC051-YC055
2005B	24		Y2	AE	29-8	SPARE	D45111P	B04			D45115J	20			YC056-YC058
2005B	24		Y2	AE	11-8	22-11-53	D41153P	B01			D45115J	20			YC059-YR328
2005R	24		Y2	AE	0-0	SPARE	D45111P	A04			D45115J	19			YC051-YC058
2005R	24		Y2	AE	0-0	22-11-53	D41153P	A01			D45115J	19			YC059-YR328
2005Z				AE	0-0	SPARE	D45111P	PERG	1F		D45115J	S/R			YC051-YC058
2005Z				AE	0-0	22-11-53	D41153P	PERG	1F		D45115J	S/R			YC059-YR328
2006B	24		Y2	AF	11-1	34-51-11	D45115J	22			D45113P	B07			ALL
2006R	24		Y2	AF	0-0	34-51-11	D45115J	21			D45113P	A07			ALL
2006Z				AF	0-0	34-51-11	D45115J	S/R			D45113P	PERG	1F		ALL
2007B	24		Y2	AG	28-9	34-51-11	D45111P	B05			D45115J	24			YC051-YC055
2007B	24		Y2	AG	29-8	34-51-11	D45111P	B05			D45115J	24			YC056-YR328
2007R	24		Y2	AG	0-0	34-51-11	D45111P	A05			D45115J	23			ALL
2007Z				AG	0-0	34-51-11	D45111P	PERG	1F		D45115J	S/R			ALL
2008B	24		Y2	AH	28-9	34-51-11	D45111P	B06			D45115J	26			YC051-YC055
2008B	24		Y2	AH	29-8	34-51-11	D45111P	B06			D45115J	26			YC056-YR328
2008R	24		Y2	AH	0-0	34-51-11	D45111P	A06			D45115J	25			ALL
2008Z				AH	0-0	34-51-11	D45111P	PERG	1F		D45115J	S/R			ALL

WIRE LIST

D280A108

91-21-11

Section W5110

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5111	286A5111			EE INTER-RACK - LEFT (E1-X TO E3-X) (continued)											
2009B	24		Y2	AI	29-5	34-51-11	D45115J	28			D45117P	B07			YC051-YC055
2009B	24		Y2	AI	30-4	34-51-11	D45115J	28			D45117P	B07			YC056-YR328
2009R	24		Y2	AI	0-0	34-51-11	D45115J	27			D45117P	A07			ALL
2009Z				AI	0-0	34-51-11	D45115J	S/R			D45117P	PERG	1F		ALL
2011B	24		Y2	AK	21-1	31-62-12	D45131P	B08			D45113P	B09			YC051-YC055
2011B	24		Y2	AK	22-0	31-62-12	D45131P	B08			D45113P	B09			YC056-YR328
2011R	24		Y2	AK	0-0	31-62-12	D45131P	A08			D45113P	A09			ALL
2011Z				AK	0-0	31-62-12	D45131P	PERG	1F		D45113P	PERG	1F		ALL
2012B	24		Y2	AL	21-1	31-62-15	D45131P	B09			D45113P	B10			YC051-YC055
2012B	24		Y2	AL	22-0	31-62-15	D45131P	B09			D45113P	B10			YC056-YR328
2012R	24		Y2	AL	0-0	31-62-15	D45131P	A09			D45113P	A10			ALL
2012Z				AL	0-0	31-62-15	D45131P	PERG	1F		D45113P	PERG	1F		ALL
2013B	24		Y2	AM	28-9	31-62-15	D45131P	B10			D45115J	30			YC051-YC055
2013B	24		Y2	AM	29-8	31-62-15	D45131P	B10			D45115J	30			YC056-YR328
2013R	24		Y2	AM	0-0	31-62-15	D45131P	A10			D45115J	29			ALL
2013Z				AM	0-0	31-62-15	D45131P	PERG	1F		D45115J	S/R			ALL
2014B	24		Y2	AN	14-2	31-62-15	D45131P	B11			D10175	2			YC051-YC055
2014B	24		Y2	AN	13-7	31-62-15	D45131P	B11			D10175	2			YC056-YR328
2014R	24		Y2	AN	0-0	31-62-15	D45131P	A11			D10175	1			ALL
2014Z				AN	0-0	31-62-15	D45131P	PERG	1F		D10175	S/R			ALL
2015B	24		Y2	AO	2-5	31-62-15	D45131P	B12			D45117P	B08			ALL
2015R	24		Y2	AO	0-0	31-62-15	D45131P	A12			D45117P	A08			ALL
2015Z				AO	0-0	31-62-15	D45131P	PERG	1F		D45117P	PERG	1F		ALL
2016B	24		Y2	AP	2-5	31-62-15	D45131P	B13			D45117P	B09			ALL
2016R	24		Y2	AP	0-0	31-62-15	D45131P	A13			D45117P	A09			ALL
2016Z				AP	0-0	31-62-15	D45131P	PERG	1F		D45117P	PERG	1F		ALL
2017B	24		Y2	AQ	21-1	31-62-15	D45131P	B14			D45113P	B11			YC051-YC055
2017B	24		Y2	AQ	22-0	31-62-15	D45131P	B14			D45113P	B11			YC056-YR328
2017R	24		Y2	AQ	0-0	31-62-15	D45131P	A14			D45113P	A11			ALL
2017Z				AQ	0-0	31-62-15	D45131P	PERG	1F		D45113P	PERG	1F		ALL
2018B	24		Y2	AR	14-2	31-62-15	D45131P	B15			D11804	2			YC051-YC055
2018B	24		Y2	AR	13-6	31-62-15	D45131P	B15			D11804	2			YC056-YR328
2018R	24		Y2	AR	0-0	31-62-15	D45131P	A15			D11804	1			ALL
2018Z				AR	0-0	31-62-15	D45131P	PERG	1F		D11804	S/R			ALL
2019B	24		Y2	AS	14-2	31-62-15	D45131P	B16			D11804	6			YC051-YC055
2019B	24		Y2	AS	13-6	31-62-15	D45131P	B16			D11804	6			YC056-YR328
2019R	24		Y2	AS	0-0	31-62-15	D45131P	A16			D11804	5			ALL
2019Z				AS	0-0	31-62-15	D45131P	PERG	1F		D11804	S/R			ALL
2020B	24		Y2	AT	2-5	34-33-11	D45111P	B07			D45117P	B10			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5110

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5111	286A5111				EE INTER-RACK - LEFT (E1-X TO E3-X) (continued)										
2020B	24	Y2	AT		2-4	34-33-11	D45111P	B07			D45117P	B10			YC056-YR328
2020R	24	Y2	AT		0-0	34-33-11	D45111P	A07			D45117P	A10			ALL
2020Z			AT		0-0	34-33-11	D45111P	PERG	1F		D45117P	PERG	1F		ALL
2021B	24	Y2	AU		2-5	SPARE	D45111P	B08			D45117P	B11			YC051-YC055
2021B	24	Y2	AU		2-4	SPARE	D45111P	B08			D45117P	B11			YC056-YR328
2021R	24	Y2	AU		0-0	SPARE	D45111P	A08			D45117P	A11			ALL
2021Z			AU		0-0	SPARE	D45111P	PERG	1F		D45117P	PERG	1F		ALL
2022B	24	Y2	AV		21-1	34-45-11	D45111P	B09			D45113P	B12			YC051-YC055
2022B	24	Y2	AV		22-0	34-45-11	D45111P	B09			D45113P	B12			YC056-YR328
2022R	24	Y2	AV		0-0	34-45-11	D45111P	A09			D45113P	A12			ALL
2022Z			AV		0-0	34-45-11	D45111P	PERG	1F		D45113P	PERG	1F		ALL
2023B	24	Y2	AW		28-9	34-55-11	D45111P	B10			D45115J	32			YC051-YC055
2023B	24	Y2	AW		29-8	34-55-11	D45111P	B10			D45115J	32			YC056-YR328
2023R	24	Y2	AW		0-0	34-55-11	D45111P	A10			D45115J	31			ALL
2023Z			AW		0-0	34-55-11	D45111P	PERG	1F		D45115J	S/R			ALL
2024B	22	X2	AX		2-5	34-61-18	D45111P	B11			D45117P	B12			YC051-YC055
2024B	22	X2	AX		2-4	34-61-18	D45111P	B11			D45117P	B12			YC056-YC058
2024B	22	X2	AX		2-6	SPARE	D45111P	CAP	Y		D45117P	B12			YC059-YR328
2024R	22	X2	AX		0-0	34-61-18	D45111P	A11			D45117P	A12			YC051-YC058
2024R	22	X2	AX		0-0	SPARE	D45111P	CAP	Y		D45117P	A12			YC059-YR328
2024Z			AX		0-0	34-61-18	D45111P	PERG	1F		D45117P	PERG	1F		YC051-YC058
2024Z			AX		0-0	SPARE	D45111P	DED			D45117P	PERG	1F		YC059-YR328
2025B	24	Y2	AY		2-5	31-35-02	D45111P	B12			D45137P	B07			YC051-YC055
2025B	24	Y2	AY		2-4	31-35-02	D45111P	B12			D45137P	B07			YC056-YR328
2025R	24	Y2	AY		0-0	31-35-02	D45111P	A12			D45137P	A07			ALL
2025Z			AY		0-0	31-35-02	D45111P	PERG	1F		D45137P	PERG	1F		ALL
2029B	24	Y2	BC		2-5	27-32-12	D45111P	B13			D45117P	B16			YC051-YC055
2029B	24	Y2	BC		2-4	27-32-12	D45111P	B13			D45117P	B16			YC056-YR328
2029R	24	Y2	BC		0-0	27-32-12	D45111P	A13			D45117P	A16			ALL
2029Z			BC		0-0	27-32-12	D45111P	PERG	1F		D45117P	PERG	1F		ALL
2030B	22	X2	BD		2-5	22-23-12	D45111P	B14			D45117P	B13			YC051-YC055
2030B	22	X2	BD		2-4	22-23-12	D45111P	B14			D45117P	B13			YC056-YL959, YN231-YN235
2030B	22	X2	BD		2-4	SPARE	D45111P	B14			D45117P	B13			YL963-YL999, YN236-YR328
2030R	22	X2	BD		0-0	22-23-12	D45111P	A14			D45117P	A13			YC051-YL959, YN231-YN235
2030R	22	X2	BD		0-0	SPARE	D45111P	A14			D45117P	A13			YL963-YL999, YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W5110

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5111		286A5111				EE INTER-RACK - LEFT (E1-X TO E3-X) (continued)										
2030Z					BD	0-0	22-23-12	D45111P	PERG	1F		D45117P	PERG	1F		YC051-YL959, YN231-YN235
2030Z					BD	0-0	SPARE	D45111P	PERG	1F		D45117P	PERG	1F		YL963-YL999, YN236-YR328
2031B	24	Y2	BE	2-5	27-32-12	D45111P	B15					D45117P	B14			YC051-YC055
2031B	24	Y2	BE	2-4	27-32-12	D45111P	B15					D45117P	B14			YC056-YR328
2031R	24	Y2	BE	0-0	27-32-12	D45111P	A15					D45117P	A14			ALL
2031Z			BE	0-0	27-32-12	D45111P	PERG	1F				D45117P	PERG	1F		ALL
2032B	24	Y2	BF	28-9	34-57-11	D45111P	B16					D45115J	36			YC051-YC055
2032B	24	Y2	BF	29-8	34-57-11	D45111P	B16					D45115J	36			YC056-YR328
2032R	24	Y2	BF	0-0	34-57-11	D45111P	A16					D45115J	35			ALL
2032Z			BF	0-0	34-57-11	D45111P	PERG	1F				D45115J	S/R			ALL
2033B	24	Y2	BG	21-1	SPARE	D45111P	B17					D45113P	B14			YC051-YC055
2033B	24	Y2	BG	22-0	SPARE	D45111P	B17					D45113P	B14			YC056-YR328
2033R	24	Y2	BG	0-0	SPARE	D45111P	A17					D45113P	A14			ALL
2033Z			BG	0-0	SPARE	D45111P	PERG	1F				D45113P	PERG	1F		ALL
2042B	24	Y2	BP	11-1	SPARE	D45115J	40					D45113P	B15			ALL
2042R	24	Y2	BP	0-0	SPARE	D45115J	39					D45113P	A15			ALL
2042Z			BP	0-0	SPARE	D45115J	S/R					D45113P	PERG	1F		ALL
2043B	24	Y2	BQ	2-5	SPARE	D45117P	B17					D45111P	B18			YC051-YC055
2043B	24	Y2	BQ	2-4	SPARE	D45117P	B17					D45111P	B18			YC056-YR328
2043R	24	Y2	BQ	0-0	SPARE	D45117P	A17					D45111P	A18			ALL
2043Z			BQ	0-0	SPARE	D45117P	PERG	1F				D45111P	PERG	1F		ALL
2044B	24	Y2	BR	21-9	27-32-12	D45113P	B13					D45117P	B18			YC051-YC055
2044B	24	Y2	BR	22-8	27-32-12	D45113P	B13					D45117P	B18			YC056-YR328
2044R	24	Y2	BR	0-0	27-32-12	D45113P	A13					D45117P	A18			ALL
2044Z			BR	0-0	27-32-12	D45113P	PERG	1F				D45117P	PERG	1F		ALL
2045B	24	Y2	BS	2-5	SPARE	D45111P	B20					D45137P	B15			YC051-YC055
2045B	24	Y2	BS	2-4	SPARE	D45111P	B20					D45137P	B15			YC056-YR328
2045R	24	Y2	BS	0-0	SPARE	D45111P	A20					D45137P	A15			ALL
2045Z			BS	0-0	SPARE	D45111P	PERG	1F				D45137P	PERG	1F		ALL
2046B	24	Y2	BT	11-3	SPARE	D45133P	B05					D45115J	50			ALL
2046R	24	Y2	BT	0-0	SPARE	D45133P	A05					D45115J	49			ALL
2046Z			BT	0-0	SPARE	D45133P	PERG	1F				D45115J	S/R			ALL
2047B	24	Y2	BU	21-3	SPARE	D45131P	B03					D45133P	B06			YC051-YC055
2047B	24	Y2	BU	22-2	SPARE	D45131P	B03					D45133P	B06			YC056-YR328
2047R	24	Y2	BU	0-0	SPARE	D45131P	A03					D45133P	A06			ALL
2047Z			BU	0-0	SPARE	D45131P	PERG	1F				D45133P	PERG	1F		ALL
2048B	24	Y2	BV	2-5	SPARE	D45111P	B19					D45137P	B16			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5110

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5111	286A5111				EE INTER-RACK - LEFT (E1-X TO E3-X) (continued)										
2048B	24	Y2	BV		2-4	SPARE	D45111P	B19			D45137P	B16			YC056-YR328
2048R	24	Y2	BV		0-0	SPARE	D45111P	A19			D45137P	A16			ALL
2048Z			BV		0-0	SPARE	D45111P	PERG	1F		D45137P	PERG	1F		ALL
2049B	24	Y2	BW		2-5	27-81-41	D45137P	B17			D45131P	B19			YC051-YC055
2049B	24	Y2	BW		2-4	27-81-41	D45137P	B17			D45131P	B19			YC056-YR328
2049R	24	Y2	BW		0-0	27-81-41	D45137P	A17			D45131P	A19			ALL
2049Z			BW		0-0	27-81-41	D45137P	PERG	1F		D45131P	PERG	1F		ALL
2050B	22	X2	BX		2-5	SPARE	D45137P	B18			D45131P	B20			YC051-YC055
2050B	22	X2	BX		2-4	SPARE	D45137P	B18			D45131P	B20			YC056-YR328
2050R	22	X2	BX		0-0	SPARE	D45137P	A18			D45131P	A20			ALL
2050Z			BX		0-0	SPARE	D45137P	PERG	1F		D45131P	PERG	1F		ALL
2052B	24	Y2	BZ		21-3	SPARE	D45131P	B06			D45133P	B07			YC051-YC052
2052B	24	Y2	BZ		28-9	34-58-11	D45115J	38			D45131P	B06			YC053-YC055
2052B	24	Y2	BZ		29-8	34-58-11	D45115J	38			D45131P	B06			YC056-YD157
2052B	24	Y2	BZ		29-8	34-58-11	D45131P	B06			D45115J	38			YD158-YR328
2052R	24	Y2	BZ		0-0	SPARE	D45131P	A06			D45133P	A07			YC051-YC052
2052R	24	Y2	BZ		0-0	34-58-11	D45115J	37			D45131P	A06			YC053-YD157
2052R	24	Y2	BZ		0-0	34-58-11	D45131P	A06			D45115J	37			YD158-YR328
2052Z			BZ		0-0	SPARE	D45131P	PERG	1F		D45133P	PERG	1F		YC051-YC052
2052Z			BZ		0-0	34-58-11	D45115J	S/R			D45131P	PERG	1F		YC053-YD157
2052Z			BZ		0-0	34-58-11	D45131P	PERG	1F		D45115J	S/R			YD158-YR328
2053B	24	Y2	CA		11-3	22-11-51	D45133P	B10			D45115J	52			ALL
2053R	24	Y2	CA		0-0	22-11-51	D45133P	A10			D45115J	51			ALL
2053Z			CA		0-0	22-11-51	D45133P	PERG	1F		D45115J	S/R			ALL
2054B	24	Y2	CB		29-5	34-55-11	D45137P	B20			D45115J	34			YC051-YC055
2054B	24	Y2	CB		30-3	34-55-11	D45137P	B20			D45115J	34			YC056-YR328
2054R	24	Y2	CB		0-0	34-55-11	D45137P	A20			D45115J	33			ALL
2054Z			CB		0-0	34-55-11	D45137P	PERG	1F		D45115J	S/R			ALL
2055B	24	Y2	CD		4-5	31-62-15	D45151P	B06			D43305P	B06			YC051-YD157
2055B	24	Y2	CD		4-5	23-27-38	D45151P	B06			D43305P	B06			YD158-YR328
2055R	24	Y2	CD		0-0	31-62-15	D45151P	A06			D43305P	A06			YC051-YD157
2055R	24	Y2	CD		0-0	23-27-38	D45151P	A06			D43305P	A06			YD158-YR328
2055Z			CD		0-0	31-62-15	D45151P	PERG	1F		D43305P	PERG	1F		YC051-YD157
2055Z			CD		0-0	23-27-38	D45151P	PERG	1F		D43305P	PERG	1F		YD158-YR328
2056B	24	Y2	CE		4-5	31-62-15	D45151P	B07			D43305P	B07			YC051-YN260
2056B	24	Y2	CE		4-5	SPARE	D45151P	B07			D43305P	B07			YN501-YR328
2056R	24	Y2	CE		0-0	31-62-15	D45151P	A07			D43305P	A07			YC051-YN260
2056R	24	Y2	CE		0-0	SPARE	D45151P	A07			D43305P	A07			YN501-YR328
2056Z			CE		0-0	31-62-15	D45151P	PERG	1F		D43305P	PERG	1F		YC051-YN260

WIRE LIST

D280A108

91-21-11

Section W5110

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5111 286A5111 EE INTER-RACK - LEFT (E1-X TO E3-X) (continued)																
2056Z					CE	0-0	SPARE	D45151P	PERG	1F		D43305P	PERG	1F		YN501-YR328
2057B	24		Y2		CF	4-5	31-62-25	D45151P	B05			D43305P	B08			YC051-YD157
2057B	24		Y2		CF	4-5	SPARE	D45151P	B05			D43305P	B08			YD158-YD170
2057R	24		Y2		CF	0-0	31-62-25	D45151P	A05			D43305P	A08			YC051-YD157
2057R	24		Y2		CF	0-0	SPARE	D45151P	A05			D43305P	A08			YD158-YD170
2057Z					CF	0-0	31-62-25	D45151P	PERG	1F		D43305P	PERG	1F		YC051-YD157
2057Z					CF	0-0	SPARE	D45151P	PERG	1F		D43305P	PERG	1F		YD158-YD170
2058B	24		Y2		CG	2-9	SPARE	D45177P	B05			D43307P	B10			YC051-YD170
2058R	24		Y2		CG	0-0	SPARE	D45177P	A05			D43307P	A10			YC051-YD170
2058Z					CG	0-0	SPARE	D45177P	PERG	1F		D43307P	PERG	1F		YC051-YD170
2059B	24		Y2		CH	2-9	SPARE	D45177P	B06			D43307P	B09			YC051-YD170
2059R	24		Y2		CH	0-0	SPARE	D45177P	A06			D43307P	A09			YC051-YD170
2059Z					CH	0-0	SPARE	D45177P	PERG	1F		D43307P	PERG	1F		YC051-YD170
2060B	24		Y2		CJ	2-9	31-35-02	D45177P	B07			D43307P	B06			ALL
2060R	24		Y2		CJ	0-0	31-35-02	D45177P	A07			D43307P	A06			ALL
2060Z					CJ	0-0	31-35-02	D45177P	PERG	1F		D43307P	PERG	1F		ALL
2061B	24		Y2		CK	4-5	31-35-02	D43305P	B05			D45151P	B08			ALL
2061R	24		Y2		CK	0-0	31-35-02	D43305P	A05			D45151P	A08			ALL
2061Z					CK	0-0	31-35-02	D43305P	PERG	1F		D45151P	PERG	1F		ALL
2062B	24		Y2		CL	2-9	23-27-12	D45157P	B08			D43307P	B04			YC051-YC055
2062B	24		Y2		CL	2-8	23-27-12	D45157P	B08			D43307P	B04			YC056-YD157
2062B	24		Y2		CL	2-8	SPARE	D45157P	B08			D43307P	B04			YD158-YR328
2062R	24		Y2		CL	0-0	23-27-12	D45157P	A08			D43307P	A04			YC051-YD157
2062R	24		Y2		CL	0-0	SPARE	D45157P	A08			D43307P	A04			YD158-YR328
2062Z					CL	0-0	23-27-12	D45157P	PERG	1F		D43307P	PERG	1F		YC051-YD157
2062Z					CL	0-0	SPARE	D45157P	PERG	1F		D43307P	PERG	1F		YD158-YR328
2063B	24		Y2		CM	32-9	SPARE	D45211J	B10			D43321P	B09			YC051-YC055
2063B	24		Y2		CM	33-7	SPARE	D45211J	B10			D43321P	B09			YC056-YD157
2063B	24		Y2		CM	33-7	SPARE	D43321P	B20			D45211J	B10			YD158-YL967, YN231-YN235, YN501-YR328
2063R	24		Y2		CM	0-0	SPARE	D45211J	A10			D43321P	A09			YC051-YD157
2063R	24		Y2		CM	0-0	SPARE	D43321P	A20			D45211J	A10			YD158-YL967, YN231-YN235, YN501-YR328
2063Z					CM	0-0	SPARE	D45211J	PERG	1F		D43321P	PERG	1F		YC051-YD157
2063Z					CM	0-0	SPARE	D43321P	PERG	1F		D45211J	PERG	1F		YD158-YL967, YN231-YN235, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W5110

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5111	286A5111			EE INTER-RACK - LEFT (E1-X TO E3-X) (continued)											
2064B	24	Y2	CN		32-9	34-61-21	D45211J	B11			D43321P	B11			YC051-YC055
2064B	24	Y2	CN		33-7	34-61-21	D45211J	B11			D43321P	B11			YC056-YR328
2064R	24	Y2	CN		0-0	34-61-21	D45211J	A11			D43321P	A11			ALL
2064Z			CN		0-0	34-61-21	D45211J	PERG	1F		D43321P	PERG	1F		ALL
2065B	24	Y2	CO		32-9	34-61-23	D45211J	B12			D43321P	B07			YC051-YC055
2065B	24	Y2	CO		33-7	34-61-23	D45211J	B12			D43321P	B07			YC056-YR328
2065R	24	Y2	CO		0-0	34-61-23	D45211J	A12			D43321P	A07			ALL
2065Z			CO		0-0	34-61-23	D45211J	PERG	1F		D43321P	PERG	1F		ALL
2066B	24	Y2	CP		2-9	34-61-18	D45177P	B08			D43307P	B01			YC051-YC058
2066B	24	Y2	CP		3-4	31-32-15	D45111P	B11			D43307P	B01			YC059-YR328
2066R	24	Y2	CP		0-0	34-61-18	D45177P	A08			D43307P	A01			YC051-YC058
2066R	24	Y2	CP		0-0	31-32-15	D45111P	A11			D43307P	A01			YC059-YR328
2066Z			CP		0-0	34-61-18	D45177P	PERG	1F		D43307P	PERG	1F		YC051-YC058
2066Z			CP		0-0	31-32-15	D45111P	PERG	1F		D43307P	PERG	1F		YC059-YR328
2067B	24	Y2	CQ		32-9	23-27-13	D45211J	B07			D43321P	B06			YC051-YC055
2067B	24	Y2	CQ		33-7	23-27-13	D45211J	B07			D43321P	B06			YC056-YD157
2067B	24	Y2	CQ		33-7	SPARE	D45211J	B07			D43321P	B06			YD158-YR328
2067R	24	Y2	CQ		0-0	23-27-13	D45211J	A07			D43321P	A06			YC051-YD157
2067R	24	Y2	CQ		0-0	SPARE	D45211J	A07			D43321P	A06			YD158-YR328
2067Z			CQ		0-0	23-27-13	D45211J	PERG	1F		D43321P	PERG	1F		YC051-YD157
2067Z			CQ		0-0	SPARE	D45211J	PERG	1F		D43321P	PERG	1F		YD158-YR328
2068B	24	Y2	CR		32-9	23-27-14	D45211J	B08			D43321P	B12			YC051-YC055
2068B	24	Y2	CR		33-7	23-27-14	D45211J	B08			D43321P	B12			YC056-YD157
2068B	24	Y2	CR		33-7	23-27-32	D45211J	B08			D43321P	B12			YD158-YR328
2068R	24	Y2	CR		0-0	23-27-14	D45211J	A08			D43321P	A12			YC051-YD157
2068R	24	Y2	CR		0-0	23-27-32	D45211J	A08			D43321P	A12			YD158-YR328
2068Z			CR		0-0	23-27-14	D45211J	PERG	1F		D43321P	PERG	1F		YC051-YD157
2068Z			CR		0-0	23-27-32	D45211J	PERG	1F		D43321P	PERG	1F		YD158-YR328
2069B	24	Y2	CS		32-9	23-27-11	D45211J	B06			D43321P	B13			YC051-YC055
2069B	24	Y2	CS		33-7	23-27-11	D45211J	B06			D43321P	B13			YC056-YD157
2069B	24	Y2	CS		33-7	23-27-39	D45211J	B06			D43321P	B13			YD158-YR328
2069R	24	Y2	CS		0-0	23-27-11	D45211J	A06			D43321P	A13			YC051-YD157
2069R	24	Y2	CS		0-0	23-27-39	D45211J	A06			D43321P	A13			YD158-YR328
2069Z			CS		0-0	23-27-11	D45211J	PERG	1F		D43321P	PERG	1F		YC051-YD157
2069Z			CS		0-0	23-27-39	D45211J	PERG	1F		D43321P	PERG	1F		YD158-YR328
2070B	24	Y2	CT		2-9	23-27-15	D43307P	B18			D45157P	B09			YC051-YC055
2070B	24	Y2	CT		2-8	23-27-15	D43307P	B18			D45157P	B09			YC056-YD157
2070B	24	Y2	CT		2-8	23-27-34	D43307P	B18			D45157P	B09			YD158-YD170
2070R	24	Y2	CT		0-0	23-27-15	D43307P	A18			D45157P	A09			YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W5110

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5111		286A5111			EE INTER-RACK - LEFT (E1-X TO E3-X) (continued)											
2070R		24		Y2	CT	0-0	23-27-34	D43307P	A18			D45157P	A09			YD158-YD170
2070Z					CT	0-0	23-27-15	D43307P	PERG	1F		D45157P	PERG	1F		YC051-YD157
2070Z					CT	0-0	23-27-34	D43307P	PERG	1F		D45157P	PERG	1F		YD158-YD170
2071B		22		X2	CU	2-9	23-32-21	D43307P	B19			D45157P	B10			YC051-YC055
2071B		22		X2	CU	2-8	23-32-21	D43307P	B19			D45157P	B10			YC056-YD170
2071B		22		X2	CU	33-7	SPARE	D43321P	B19			D45211J	B19			YL951-YR328
2071R		22		X2	CU	0-0	23-32-21	D43307P	A19			D45157P	A10			YC051-YD170
2071R		22		X2	CU	0-0	SPARE	D43321P	A19			D45211J	A19			YL951-YR328
2071Z					CU	0-0	23-32-21	D43307P	PERG	1F		D45157P	PERG	1F		YC051-YD170
2071Z					CU	0-0	SPARE	D43321P	PERG	1F		D45211J	PERG	1F		YL951-YR328
2072B		24		Y2	CV	31-10	SPARE	D45211J	B13			D45177P	B09			YC051-YC055
2072B		24		Y2	CV	32-8	SPARE	D45211J	B13			D45177P	B09			YC056-YD170
2072R		24		Y2	CV	0-0	SPARE	D45211J	A13			D45177P	A09			YC051-YD170
2072Z					CV	0-0	SPARE	D45211J	PERG	1F		D45177P	PERG	1F		YC051-YD170
2073B		24		Y2	CW	2-9	34-61-23	D43321P	B08			D45177P	B10			ALL
2073R		24		Y2	CW	0-0	34-61-23	D43321P	A08			D45177P	A10			ALL
2073Z					CW	0-0	34-61-23	D43321P	PERG	1F		D45177P	PERG	1F		ALL
2074B		24		Y2	CX	2-9	23-27-14	D43307P	B07			D45177P	B03			YC051-YD157
2074B		24		Y2	CX	2-9	23-27-32	D43307P	B07			D45177P	B03			YD158-YR328
2074R		24		Y2	CX	0-0	23-27-14	D43307P	A07			D45177P	A03			YC051-YD157
2074R		24		Y2	CX	0-0	23-27-32	D43307P	A07			D45177P	A03			YD158-YR328
2074Z					CX	0-0	23-27-14	D43307P	PERG	1F		D45177P	PERG	1F		YC051-YD157
2074Z					CX	0-0	23-27-32	D43307P	PERG	1F		D45177P	PERG	1F		YD158-YR328
2075B		24		Y2	CY	2-9	23-27-14	D43307P	B08			D45177P	B04			YC051-YD157
2075B		24		Y2	CY	2-9	31-33-01	D45177P	B04			D43307P	B08			YD158-YL999, YN232-YR328
2075B		24		Y2	CY	2-9	SPARE	D45177P	B04			D43307P	B08			YN231
2075R		24		Y2	CY	0-0	23-27-14	D43307P	A08			D45177P	A04			YC051-YD157
2075R		24		Y2	CY	0-0	31-33-01	D45177P	A04			D43307P	A08			YD158-YL999, YN232-YR328
2075R		24		Y2	CY	0-0	SPARE	D45177P	A04			D43307P	A08			YN231
2075Z					CY	0-0	23-27-14	D43307P	PERG	1F		D45177P	PERG	1F		YC051-YD157
2075Z					CY	0-0	31-33-01	D45177P	PERG	1F		D43307P	PERG	1F		YD158-YL999, YN232-YR328
2075Z					CY	0-0	SPARE	D45177P	PERG	1F		D43307P	PERG	1F		YN231
2077B		24		Y2	DB	21-9	22-23-12	D45117P	B19			D45113P	B08			YC051-YC055
2077B		24		Y2	DB	22-8	22-23-12	D45117P	B19			D45113P	B08			YC056-YR328
2077R		24		Y2	DB	0-0	22-23-12	D45117P	A19			D45113P	A08			ALL
2077Z					DB	0-0	22-23-12	D45117P	PERG	1F		D45113P	PERG	1F		ALL

WIRE LIST

D280A108

91-21-11

Section W5110

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5111	286A5111				EE INTER-RACK - LEFT (E1-X TO E3-X) (continued)										
2079B	24	Y2	DD		33-7	23-27-32	D45211J	B14			D43321P	B04			YD158-YN260
2079B	24	Y2	DD		33-7	SPARE	D45211J	B14			D43321P	B04			YN501-YR328
2079R	24	Y2	DD		0-0	23-27-32	D45211J	A14			D43321P	A04			YD158-YN260
2079R	24	Y2	DD		0-0	SPARE	D45211J	A14			D43321P	A04			YN501-YR328
2079Z			DD		0-0	23-27-32	D45211J	PERG	1F		D43321P	PERG	1F		YD158-YN260
2079Z			DD		0-0	SPARE	D45211J	PERG	1F		D43321P	PERG	1F		YN501-YR328
2080B	24	Y2	DE		33-7	SPARE	D45211J	B15			D43321P	B05			YD158-YR328
2080R	24	Y2	DE		0-0	SPARE	D45211J	A15			D43321P	A05			YD158-YR328
2080Z			DE		0-0	SPARE	D45211J	PERG	1F		D43321P	PERG	1F		YD158-YR328
2082B	24	Y2	DG		33-7	SPARE	D43321P	B10			D45211J	B02			YD158-YR328
2082R	24	Y2	DG		0-0	SPARE	D43321P	A10			D45211J	A02			YD158-YR328
2082Z			DG		0-0	SPARE	D43321P	PERG	1F		D45211J	PERG	1F		YD158-YR328
2083B	24	Y2	DH		33-7	34-61-25	D45211J	B03			D43321P	B01			YD158-YN260
2083B	24	Y2	DH		33-7	SPARE	D45211J	B03			D43321P	B01			YN501-YR328
2083R	24	Y2	DH		0-0	34-61-25	D45211J	A03			D43321P	A01			YD158-YN260
2083R	24	Y2	DH		0-0	SPARE	D45211J	A03			D43321P	A01			YN501-YR328
2083Z			DH		0-0	34-61-25	D45211J	PERG	1F		D43321P	PERG	1F		YD158-YN260
2083Z			DH		0-0	SPARE	D45211J	PERG	1F		D43321P	PERG	1F		YN501-YR328
2084B	24	Y2	DI		33-7	34-61-25	D45211J	B04			D43321P	B02			YD158-YN260
2084B	24	Y2	DI		33-7	SPARE	D45211J	B04			D43321P	B02			YN501-YR328
2084R	24	Y2	DI		0-0	34-61-25	D45211J	A04			D43321P	A02			YD158-YN260
2084R	24	Y2	DI		0-0	SPARE	D45211J	A04			D43321P	A02			YN501-YR328
2084Z			DI		0-0	34-61-25	D45211J	PERG	1F		D43321P	PERG	1F		YD158-YN260
2084Z			DI		0-0	SPARE	D45211J	PERG	1F		D43321P	PERG	1F		YN501-YR328
2085B	24	Y2	DJ		33-7	34-61-25	D45211J	B05			D43321P	B03			YD158-YN260
2085B	24	Y2	DJ		33-7	SPARE	D45211J	B05			D43321P	B03			YN501-YR328
2085R	24	Y2	DJ		0-0	34-61-25	D45211J	A05			D43321P	A03			YD158-YN260
2085R	24	Y2	DJ		0-0	SPARE	D45211J	A05			D43321P	A03			YN501-YR328
2085Z			DJ		0-0	34-61-25	D45211J	PERG	1F		D43321P	PERG	1F		YD158-YN260
2085Z			DJ		0-0	SPARE	D45211J	PERG	1F		D43321P	PERG	1F		YN501-YR328
2086B	24	Y2	DK		2-5	SPARE	D45151P	B03			D45137P	B02			YD158-YD170
2086B	24	Y2	DK		2-5	31-62-15	D45151P	B03			D45137P	B02			YL951-YR328
2086R	24	Y2	DK		0-0	SPARE	D45151P	A03			D45137P	A02			YD158-YD170
2086R	24	Y2	DK		0-0	31-62-15	D45151P	A03			D45137P	A02			YL951-YR328
2086Z			DK		0-0	SPARE	D45151P	PERG	1F		D45137P	PERG	1F		YD158-YD170
2086Z			DK		0-0	31-62-15	D45151P	PERG	1F		D45137P	PERG	1F		YL951-YR328
2087B	24	Y2	DL		2-5	SPARE	D45151P	B04			D45137P	B05			YD158-YD170
2087B	24	Y2	DL		2-5	31-62-15	D45151P	B04			D45137P	B05			YL951-YR328
2087R	24	Y2	DL		0-0	SPARE	D45151P	A04			D45137P	A05			YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W5110

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5111 286A5111 EE INTER-RACK - LEFT (E1-X TO E3-X) (continued)																
2087R	24		Y2	DL		0-0	31-62-15	D45151P	A04			D45137P	A05			YL951-YR328
2087Z				DL		0-0	SPARE	D45151P	PERG	1F		D45137P	PERG	1F		YD158-YD170
2087Z				DL		0-0	31-62-15	D45151P	PERG	1F		D45137P	PERG	1F		YL951-YR328
2090B	22		X2	DP		32-9	23-27-15	D43321P	B16			D45211J	B16			YC051-YC055
2090B	22		X2	DP		33-7	23-27-15	D43321P	B16			D45211J	B16			YC056-YD157
2090R	22		X2	DP		0-0	23-27-15	D43321P	A16			D45211J	A16			YC051-YD157
2090Z				DP		0-0	23-27-15	D43321P	PERG	1F		D45211J	PERG	1F		YC051-YD157
2091B	24		Y2	DQ		32-9	23-15-12	D43321P	B17			D45211J	B17			YC051-YC055
2091B	24		Y2	DQ		33-7	23-15-12	D43321P	B17			D45211J	B17			YC056-YD157
2091B	24		Y2	DQ		33-7	SPARE	D43321P	B17			D45211J	B17			YD158-YD170
2091R	24		Y2	DQ		0-0	23-15-12	D43321P	A17			D45211J	A17			YC051-YD157
2091R	24		Y2	DQ		0-0	SPARE	D43321P	A17			D45211J	A17			YD158-YD170
2091Z				DQ		0-0	23-15-12	D43321P	PERG	1F		D45211J	PERG	1F		YC051-YD157
2091Z				DQ		0-0	SPARE	D43321P	PERG	1F		D45211J	PERG	1F		YD158-YD170
2092B	24		Y2	DR		33-7	SPARE	D45211J	B16			D43321P	B18			YD158-YN260
2092B	22		X2	DR		33-7	44-21-20	D45211J	B16			D43321P	B18			YN501-YR328
2092R	24		Y2	DR		0-0	SPARE	D45211J	A16			D43321P	A18			YD158-YN260
2092R	22		X2	DR		0-0	44-21-20	D45211J	A16			D43321P	A18			YN501-YR328
2092Z				DR		0-0	SPARE	D45211J	PERG	1F		D43321P	PERG	1F		YD158-YN260
2092Z				DR		0-0	44-21-20	D45211J	PERG	1F		D43321P	PERG	1F		YN501-YR328
2093B	24		Y2	DS		32-4	34-45-21	D45115J	48			D43305P	B10			YD158-YR328
2093R	24		Y2	DS		0-0	34-45-21	D45115J	47			D43305P	A10			YD158-YR328
2093Z				DS		0-0	34-45-21	D45115J	S/R			D43305P	PERG	1F		YD158-YR328
2099B	24		Y2	DY		33-7	SPARE	D43321P	B15			D45211J	B18			YD158-YL967, YN231-YN235, YN501-YR328
2099R	24		Y2	DY		0-0	SPARE	D43321P	A15			D45211J	A18			YD158-YL967, YN231-YN235, YN501-YR328
2099Z				DY		0-0	SPARE	D43321P	PERG	1F		D45211J	PERG	1F		YD158-YL967, YN231-YN235, YN501-YR328
2102B	22		X2	EP		33-7	44-21-20	D43321P	B09			D45211J	B20			YN501-YR328
2102R	22		X2	EP		0-0	44-21-20	D43321P	A09			D45211J	A20			YN501-YR328
2102Z				EP		0-0	44-21-20	D43321P	PERG	1F		D45211J	PERG	1F		YN501-YR328
2123B	24		Y2	FC		32-8	23-27-39	D45211J	B09			D45177P	B09			YL951-YL954, YN231-YN235
2123R	24		Y2	FC		0-0	23-27-39	D45211J	A09			D45177P	A09			YL951-YL954, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W5110

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5111	286A5111			EE INTER-RACK - LEFT (E1-X TO E3-X) (continued)											
2123Z				FC	0-0	23-27-39	D45211J	PERG	1F		D45177P	PERG	1F		YL951-YL954, YN231-YN235
2124B	24	Y2	FD		33-7	23-27-39	D45211J	B13			D43321P	B17			YL951-YL954, YN231-YN235
2124R	24	Y2	FD		0-0	23-27-39	D45211J	A13			D43321P	A17			YL951-YL954, YN231-YN235
2124Z			FD		0-0	23-27-39	D45211J	PERG	1F		D43321P	PERG	1F		YL951-YL954, YN231-YN235
2125B	24	Y2	FE		32-8	23-27-39	D45211J	B17			D45177P	B05			YL951-YL954, YN231-YN235
2125R	24	Y2	FE		0-0	23-27-39	D45211J	A17			D45177P	A05			YL951-YL954, YN231-YN235
2125Z			FE		0-0	23-27-39	D45211J	PERG	1F		D45177P	PERG	1F		YL951-YL954, YN231-YN235
2126B	24	Y2	FF		2-9	23-27-39	D45177P	B06			D43307P	B18			YL951-YL954, YN231-YN235
2126R	24	Y2	FF		0-0	23-27-39	D45177P	A06			D43307P	A18			YL951-YL954, YN231-YN235
2126Z			FF		0-0	23-27-39	D45177P	PERG	1F		D43307P	PERG	1F		YL951-YL954, YN231-YN235
2127B	24	Y2	FG		2-9	SPARE	D43307P	B19			D45177P	B08			YL951-YL967
2127B	24	Y2	FG		2-9	31-35-02	D43307P	B19			D45177P	B08			YN231-YN235
2127R	24	Y2	FG		0-0	SPARE	D43307P	A19			D45177P	A08			YL951-YL967
2127R	24	Y2	FG		0-0	31-35-02	D43307P	A19			D45177P	A08			YN231-YN235
2127Z			FG		0-0	SPARE	D43307P	PERG	1F		D45177P	PERG	1F		YL951-YL967
2127Z			FG		0-0	31-35-02	D43307P	PERG	1F		D45177P	PERG	1F		YN231-YN235
W5112	286A5112			P91 (AFT DISC) TO E/E BAY											
0003	16	PA			60-4	25-51-21	D40256P	F			D11284	20			YC051-YC055
0003	16	PA			60-7	25-51-21	D40256P	F			D11284	20			YC056-YL999, YR301-YR328
0004	16	PA			60-4	25-51-21	D40256P	G			D11284	22			YC051-YC055
0004	16	PA			60-7	25-51-21	D40256P	G			D11284	22			YC056-YL999, YR301-YR328
0005	16	PA			60-4	25-51-21	D40256P	H			D11284	24			YC051-YC055
0005	16	PA			60-7	25-51-21	D40256P	H			D11284	24			YC056-YL999, YR301-YR328
0006	22	PA			60-4	25-51-21	D40256P	A01			D11284	10			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5110

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W5112	286A5112	P91 (AFT DISC) TO E/E BAY (continued)													
0006	22 PA		60-7	25-51-21	D40256P	A01			D11284	10				YC056-YL999, YR301-YR328	
0007	20 PA		2-3	25-51-21	GD02552	DC..	1		D11284	12				YC051-YC055	
0007	20 PA		2-2	25-51-21	GD02552	DC..	1		D11284	12				YC056-YL999, YR301-YR328	
0008	16 PA		2-3	25-51-21	GD02552	AC..	1		D11284	14				YC051-YC055	
0008	16 PA		2-2	25-51-21	GD02552	AC..	1		D11284	14				YC056-YL999, YR301-YR328	
0009	16 PA		2-3	25-51-21	GD02552	AC..	1		D11284	16				YC051-YC055	
0009	16 PA		2-2	25-51-21	GD02552	AC..	1		D11284	16				YC056-YL999, YR301-YR328	
0010	16 PA		2-3	25-51-21	GD02552	ST..	1		D11284	18				YC051-YC055	
0010	16 PA		2-2	25-51-21	GD02552	ST..	1		D11284	18				YC056-YL999, YR301-YR328	
0011	22 PA		39-9	25-51-21	D11284		3		D10878	3				YC051-YC055	
0011	22 PA		40-4	25-51-21	D11284		3		D10878	3				YC056-YL999, YR301-YR328	
0012	22 PA		39-9	25-51-21	D11284		4		D10878	4				YC051-YC055	
0012	22 PA		40-4	25-51-21	D11284		4		D10878	4				YC056-YL999, YR301-YR328	
0013	22 PA		39-9	25-51-21	D11284		5		D10878	5				YC051-YC055	
0013	22 PA		40-4	25-51-21	D11284		5		D10878	5				YC056-YL999, YR301-YR328	
0014	22 PA		39-9	25-51-21	D11284		7		D10878	7				YC051-YC055	
0014	22 PA		40-4	25-51-21	D11284		7		D10878	7				YC056-YL999, YR301-YR328	
0015	22 PA		39-9	25-51-21	D11284		8		D10878	8				YC051-YC055	
0015	22 PA		40-4	25-51-21	D11284		8		D10878	8				YC056-YL999, YR301-YR328	
0016	22 PA		39-9	25-51-21	D11284		9		D10878	9				YC051-YC055	
0016	22 PA		40-4	25-51-21	D11284		9		D10878	9				YC056-YL999, YR301-YR328	
0017	20 PA		2-4	25-51-21	GD11830	ST..	1		D10878	1				YC051-YC055	
0017	20 PA		2-9	25-51-21	GD11830	ST..	1		D10878	1				YC056-YL999, YR301-YR328	
0018	20 PA		2-4	25-51-21	GD11830	DC..	1		D10878	2				YC051-YC055	
0018	20 PA		2-9	25-51-21	GD11830	DC..	1		D10878	2				YC056-YL999, YR301-YR328	
0019	22 PA		43-9	25-51-21	D11284		6		S01084	1C	B			YC051-YC055	

WIRE LIST

D280A108

91-21-11

Section W5110

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5112	286A5112				P91 (AFT DISC) TO E/E BAY (continued)										
0019	22		PA		44-0	25-51-21	D11284		6		S01084	1C	B		YC056-YL999, YR301-YR328
0020	22		PA		22-7	25-51-21	S01084	1NC	B		D10878	6			YC051-YC055
0020	22		PA		23-0	25-51-21	S01084	1NC	B		D10878	6			YC056-YL999, YR301-YR328
0214	20		PA		10-6	28-23-11	R00962	X1	D		D49996P	A10			YD160-YR328
0215	20		PA		10-5	28-23-11	R00962	X2	D		D49996P	B10			YD160-YR328
0501	20		PA		7-1	24-53-11	D11434		1		T00010	HV	E		ALL
0502	20		PA		86-7	38-41-13	D40256P		A03		D01986	1			YC051-YD158
0502	20		PA		86-10	38-41-13	D40256P		A03		D01986	1			YD160-YL999, YR301-YR328
0502	20		PA		67-3	38-41-13	D40256P		A03		D01986	1			YN231-YN501
0503	20		PA		86-7	38-41-13	D40256P		B03		D01986	2			YC051-YD158
0503	20		PA		86-10	38-41-13	D40256P		B03		D01986	2			YD160-YL999, YR301-YR328
0503	20		PA		67-3	38-41-13	D40256P		B03		D01986	2			YN231-YN501
0504	20		PA		86-7	38-41-13	D40256P		A04		D01986	3			YC051-YD158
0504	20		PA		86-10	38-41-13	D40256P		A04		D01986	3			YD160-YL999, YR301-YR328
0504	20		PA		67-3	38-41-13	D40256P		A04		D01986	3			YN231-YN501
0505	20		PA		3-11	24-41-11	D11434		21		D40342P	H			ALL
0506	18		PA		3-11	24-32-11	D11434		27		D40934P	J			ALL
0507	18		PA		3-11	24-32-11	D11434		28		D40934P	F			ALL
0508	18		PA		3-11	24-32-11	D11434		29		D40934P	G			ALL
0510	20		PA		2-11	38-41-13	D01986		5		GD00028	ST..	1		YC051-YD158
0510	20		PA		3-1	38-41-13	D01986		5		GD00028	ST..	1		YD160-YR328
0511	20		PA		17-5	38-41-13	D12348		= 1	VG	D01990	2			YC051-YC055
0511	20		PA		17-6	38-41-13	D12348		= 1	VG	D01990	2			YC056-YD158
0511	20		PA		17-8	38-41-13	D12348		= 1	VG	D01990	2			YD160-YL999, YR301-YR328
0511	20		PA		17-7	38-41-13	D12348		= 1	VG	D01990	2			YN231-YN501
0512	20		PA		3-8	38-41-13	D01990		3		GD00070	AC..	1		YC051-YD158
0512	20		PA		3-1	38-41-13	D01990		3		GD00070	AC..	1		YD160-YR328
0513	20		PA		3-11	28-23-11	D11434		2		D40342P	A03			ALL
0514	20		PA		3-11	28-23-11	D11434		13		D40342P	A04			ALL
0515	20		PA		3-11	28-23-11	D11434		12		D40342P	A05			ALL
0516	18		PA		3-11	38-32-12	D11434		39		D40342P	F			ALL
0517	20		PA		3-11	38-32-12	D11434		23		D40342P	B03			ALL

WIRE LIST

D280A108

91-21-11

Section W5110

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W5112	286A5112	P91 (AFT DISC) TO E/E BAY (continued)													
0518	20	PA		96-9 38-41-13	D40256P	B04			D12346	= 1	VY			YC051-YL999, YR301-YR328	
0518	20	PA		77-2 38-41-13	D40256P	B04			D12346	= 1	VY			YN231-YN501	
3201B	20	PC	YA	4-0 28-23-11	D11434	11			D49996P	A03				ALL	
3201R	20	PC	YA	0-0 28-23-11	D11434	9			D49996P	A01				ALL	
3201Y	20	PC	YA	0-0 28-23-11	D11434	10			D49996P	A02				ALL	
3202B	18	PC	YB	4-0 28-23-11	D11434	43			D49996P	H				YC051-YD158	
3202B	18	PC	YB	9-10 28-23-11	D11434	43			R00962	C2	E			YD160-YR328	
3202R	18	PC	YB	0-0 28-23-11	D11434	41			D49996P	F				YC051-YD158	
3202R	18	PC	YB	0-0 28-23-11	D11434	41			R00962	A2	E			YD160-YR328	
3202Y	18	PC	YB	0-0 28-23-11	D11434	42			D49996P	G				YC051-YD158	
3202Y	18	PC	YB	0-0 28-23-11	D11434	42			R00962	B2	E			YD160-YR328	
3203B	20	PC	YC	4-0 28-23-11	D11434	26			D49996P	B03				ALL	
3203R	20	PC	YC	0-0 28-23-11	D11434	24			D49996P	B01				ALL	
3203Y	20	PC	YC	0-0 28-23-11	D11434	25			D49996P	B02				ALL	
3205B	18	PC	YE	10-7 28-23-11	R00962	C1	E		D49996P	H				YD160-YR328	
3205R	18	PC	YE	0-0 28-23-11	R00962	A1	E		D49996P	F				YD160-YR328	
3205Y	18	PC	YE	0-0 28-23-11	R00962	B1	E		D49996P	G				YD160-YR328	
4101B	20	PD	N6	10-1 24-21-11	D40342P	B01			D11434	18				ALL	
4101G	20	PD	N6	0-0 24-21-11	D40342P	A02			GD03200	AC..	1A			ALL	
4101R	20	PD	N6	0-0 24-21-11	D40342P	A01			D11434	16				ALL	
4101Y	20	PD	N6	0-0 24-21-11	D40342P	B02			D11434	17				ALL	
5501	22	PA		3-11 21-27-31	D11434	8			D40934P	A01				ALL	
W5115	286A5115	AUDIO ENTERTAINMENT - E4-2 SHELF TO AUDIO INTEGRATION BRKT AB0410 -MAS													
0001	20	PA		0-6 23-34-01	D10527C	2			SM00001		S			YL951-YL968, YN231-YN236	
0001	20	PA		0-6 44-21-26	D10527C	2			SM00001		S			YN501-YR328	
0002	20	PA		7-5 23-34-01	D10527C	3			GD03404	AC..	1			YL951-YL968, YN231-YN236	
0002	20	PA		7-5 44-21-26	D10527C	3			GD03404	AC..	1			YN501-YR328	
0003	20	PA		7-5 23-34-01	D10527C	4			GD03404	ST..	1			YL951-YL968, YN231-YN236	
0003	20	PA		7-5 44-21-26	D10527C	4			GD03404	ST..	1			YN501-YR328	
0004	22	PA		3-4 23-34-01	D10527B	C09			SM00002		S			YL951-YL968, YN231-YN236	
0004	22	PA		4-10 44-21-26	D10527B	C09			D12163P	21				YN501-YR328	
0007	20	PA		4-4 23-34-01	SM00001		S		D12165P	1				YL951-YL968, YN231-YN236	

WIRE LIST

D280A108

91-21-11

Section W5110

Page 18

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W5115	286A5115				AUDIO ENTERTAINMENT - E4-2 SHELF TO AUDIO INTEGRATION BRKT AB0410 -MAS (continued)												
0007	20		PA		4-4	44-21-26		SM00001		S		D12165P	1			YN501-YR328	
0008	22		PA		2-0	23-34-01		SM00002		S		D12165P	2			YL951-YL968, YN231-YN236	
0009	22		PA		2-1	23-34-01		SM00002		S		D12163P	21			YL951-YL968, YN231-YN236	
0015	22		PA		4-11	23-34-02		D10527A	B12			D12169P	2			YL951-YL968, YN231-YN236	
0015	22		PA		4-11	44-21-26		D10527A	B12			D12169P	2			YN501-YR328	
0017	22		PA		4-11	23-34-02		D10527A	B08			D12169P	19			YL951-YL968, YN231-YN236	
0017	22		PA		4-11	44-21-26		D10527A	B08			D12169P	19			YN501-YR328	
0018	22		PA		5-0	23-34-02		D10527A	B14			D12171P	1			YL951-YL968, YN231-YN236	
0018	22		PA		5-0	44-21-26		D10527A	B14			D12171P	1			YN501-YR328	
0019	22		PA		5-0	23-34-02		D10527A	B10			D12171P	18			YL951-YL968, YN231-YN236	
0019	22		PA		5-0	44-21-26		D10527A	B10			D12171P	18			YN501-YR328	
0020	20		PA		9-4	23-34-02		SM00001		S		D12211P	2			YL951-YL956	
0020	20		PA		4-7	23-34-02		SM00001		S		D12211P	2			YL957-YL968, YN231-YN236	
0020	20		PA		4-7	44-21-26		SM00001		S		D12211P	2			YN501-YR328	
0029	22		PA		3-4	44-21-26		D10527B	D09			SM00003		S		YN501-YR328	
0030	22		PA		3-4	44-21-26		D10527B	D10			SM00003		S		YN501-YR328	
0031	22		PA		3-4	44-21-26		D10527B	D11			SM00003		S		YN501-YR328	
0032	22		PA		2-1	44-21-26		D12163P	26			SM00003		S		YN501-YR328	
2501B	22	X2	AA		4-10	23-34-01		D10527B	B01			D12165P	10			YL951-YL968, YN231-YN236	
2501B	22	X2	AA		4-10	44-21-26		D10527B	B01			D12165P	10			YN501-YR328	
2501R	22	X2	AA		0-0	23-34-01		D10527B	A01			D12165P	9			YL951-YL968, YN231-YN236	
2501R	22	X2	AA		0-0	44-21-26		D10527B	A01			D12165P	9			YN501-YR328	
2501Z			AA		0-0	23-34-01		D10527B			AG	D12165P	PERS	1A		YL951-YL968, YN231-YN236	
2501Z			AA		0-0	44-21-26		D10527B			AG	D12165P	PERS	1A		YN501-YR328	
2502B	22	X2	AB		4-10	23-34-01		D10527B	D01			D12165P	12			YL951-YL968, YN231-YN236	
2502B	22	X2	AB		4-10	44-21-26		D10527B	D01			D12165P	12			YN501-YR328	
2502R	22	X2	AB		0-0	23-34-01		D10527B	C01			D12165P	11			YL951-YL968, YN231-YN236	

WIRE LIST

D280A108

91-21-11

Section W5110

Page 19

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W5115	286A5115	AUDIO ENTERTAINMENT - E4-2 SHELF TO AUDIO INTEGRATION BRKT AB0410 -MAS (continued)													
2502R	22	X2	AB	0-0	44-21-26	D10527B	C01		D12165P	11				YN501-YR328	
2502Z			AB	0-0	23-34-01	D10527B		AG	D12165P	PERS	1A			YL951-YL968,	
														YN231-YN236	
2502Z			AB	0-0	44-21-26	D10527B		AG	D12165P	PERS	1A			YN501-YR328	
2503B	22	X2	AC	4-10	23-34-01	D10527B	B02		D12165P	14				YL951-YL968,	
														YN231-YN236	
2503B	22	X2	AC	4-10	44-21-26	D10527B	B02		D12165P	14				YN501-YR328	
2503R	22	X2	AC	0-0	23-34-01	D10527B	A02		D12165P	13				YL951-YL968,	
														YN231-YN236	
2503R	22	X2	AC	0-0	44-21-26	D10527B	A02		D12165P	13				YN501-YR328	
2503Z			AC	0-0	23-34-01	D10527B		AG	D12165P	PERS	1A			YL951-YL968,	
														YN231-YN236	
2503Z			AC	0-0	44-21-26	D10527B		AG	D12165P	PERS	1A			YN501-YR328	
2504B	22	X2	AD	4-10	23-34-01	D10527B	D02		D12165P	16				YL951-YL968,	
														YN231-YN236	
2504B	22	X2	AD	4-10	44-21-26	D10527B	D02		D12165P	16				YN501-YR328	
2504R	22	X2	AD	0-0	23-34-01	D10527B	C02		D12165P	15				YL951-YL968,	
														YN231-YN236	
2504R	22	X2	AD	0-0	44-21-26	D10527B	C02		D12165P	15				YN501-YR328	
2504Z			AD	0-0	23-34-01	D10527B		AH	D12165P	PERS	1A			YL951-YL968,	
														YN231-YN236	
2504Z			AD	0-0	44-21-26	D10527B		AH	D12165P	PERS	1A			YN501-YR328	
2505B	22	X2	AE	4-10	23-34-01	D10527B	B03		D12165P	27				YL951-YL968,	
														YN231-YN236	
2505B	22	X2	AE	4-10	44-21-26	D10527B	B03		D12165P	27				YN501-YR328	
2505R	22	X2	AE	0-0	23-34-01	D10527B	A03		D12165P	26				YL951-YL968,	
														YN231-YN236	
2505R	22	X2	AE	0-0	44-21-26	D10527B	A03		D12165P	26				YN501-YR328	
2505Z			AE	0-0	23-34-01	D10527B		AH	D12165P	PERS	1A			YL951-YL968,	
														YN231-YN236	
2505Z			AE	0-0	44-21-26	D10527B		AH	D12165P	PERS	1A			YN501-YR328	
2506B	22	X2	AF	4-10	23-34-01	D10527B	D03		D12165P	29				YL951-YL968,	
														YN231-YN236	
2506B	22	X2	AF	4-10	44-21-26	D10527B	D03		D12165P	29				YN501-YR328	
2506R	22	X2	AF	0-0	23-34-01	D10527B	C03		D12165P	28				YL951-YL968,	
														YN231-YN236	
2506R	22	X2	AF	0-0	44-21-26	D10527B	C03		D12165P	28				YN501-YR328	
2506Z			AF	0-0	23-34-01	D10527B		AH	D12165P	PERS	1A			YL951-YL968,	
														YN231-YN236	

WIRE LIST

D280A108

91-21-11

Section W5110

Page 20

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5115	286A5115			AUDIO ENTERTAINMENT - E4-2 SHELF TO AUDIO INTEGRATION BRKT AB0410 -MAS (continued)											
2506Z				AF	0-0	44-21-26	D10527B			AH	D12165P	PERS	1A		YN501-YR328
2507B	22	X2		AG	4-10	23-34-01	D10527B	B04			D12165P	31			YL951-YL968, YN231-YN236
2507B	22	X2		AG	4-10	44-21-26	D10527B	B04			D12165P	31			YN501-YR328
2507R	22	X2		AG	0-0	23-34-01	D10527B	A04			D12165P	30			YL951-YL968, YN231-YN236
2507R	22	X2		AG	0-0	44-21-26	D10527B	A04			D12165P	30			YN501-YR328
2507Z				AG	0-0	23-34-01	D10527B			AI	D12165P	PERS	1A		YL951-YL968, YN231-YN236
2507Z				AG	0-0	44-21-26	D10527B			AI	D12165P	PERS	1A		YN501-YR328
2508B	22	X2		AH	4-10	23-34-01	D10527B	D04			D12165P	33			YL951-YL968, YN231-YN236
2508B	22	X2		AH	4-10	44-21-26	D10527B	D04			D12165P	33			YN501-YR328
2508R	22	X2		AH	0-0	23-34-01	D10527B	C04			D12165P	32			YL951-YL968, YN231-YN236
2508R	22	X2		AH	0-0	44-21-26	D10527B	C04			D12165P	32			YN501-YR328
2508Z				AH	0-0	23-34-01	D10527B			AI	D12165P	PERS	1A		YL951-YL968, YN231-YN236
2509B	22	X2		AI	4-9	23-34-01	D10527B	B05			D12167P	10			YN501-YR328
2509B	22	X2		AI	4-9	44-21-26	D10527B	B05			D12167P	10			YL951-YL968, YN231-YN236
2509R	22	X2		AI	0-0	23-34-01	D10527B	A05			D12167P	9			YN501-YR328
2509Z				AI	0-0	44-21-26	D10527B			AI	D12167P	PERS	1A		YL951-YL968, YN231-YN236
2509Z				AI	0-0	44-21-26	D10527B			AI	D12167P	PERS	1A		YN501-YR328
2510B	22	X2		AJ	4-9	23-34-01	D10527B	D05			D12167P	12			YL951-YL968, YN231-YN236
2510B	22	X2		AJ	4-9	44-21-26	D10527B	D05			D12167P	12			YN501-YR328
2510R	22	X2		AJ	0-0	23-34-01	D10527B	C05			D12167P	11			YL951-YL968, YN231-YN236
2510R	22	X2		AJ	0-0	44-21-26	D10527B	C05			D12167P	11			YN501-YR328
2510Z				AJ	0-0	23-34-01	D10527B			AJ	D12167P	PERS	1A		YL951-YL968, YN231-YN236
2510Z				AJ	0-0	44-21-26	D10527B			AJ	D12167P	PERS	1A		YN501-YR328
2511B	22	X2		AK	4-9	23-34-01	D10527B	B06			D12167P	14			YL951-YL968, YN231-YN236

WIRE LIST

D280A108

91-21-11

Section W5110

Page 21

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	
W5115	286A5115			AUDIO ENTERTAINMENT - E4-2 SHELF TO AUDIO INTEGRATION BRKT AB0410 -MAS (continued)										
2511B	22	X2	AK	4-9	44-21-26	D10527B	B06			D12167P	14			YN501-YR328
2511R	22	X2	AK	0-0	23-34-01	D10527B	A06			D12167P	13			YL951-YL968, YN231-YN236
2511R	22	X2	AK	0-0	44-21-26	D10527B	A06			D12167P	13			YN501-YR328
2511Z			AK	0-0	23-34-01	D10527B			AJ	D12167P	PERS	1A		YL951-YL968, YN231-YN236
2511Z			AK	0-0	44-21-26	D10527B			AJ	D12167P	PERS	1A		YN501-YR328
2512B	22	X2	AL	4-9	23-34-01	D10527B	D06			D12167P	16			YL951-YL968, YN231-YN236
2512B	22	X2	AL	4-9	44-21-26	D10527B	D06			D12167P	16			YN501-YR328
2512R	22	X2	AL	0-0	23-34-01	D10527B	C06			D12167P	15			YL951-YL968, YN231-YN236
2512R	22	X2	AL	0-0	44-21-26	D10527B	C06			D12167P	15			YN501-YR328
2512Z			AL	0-0	23-34-01	D10527B			AJ	D12167P	PERS	1A		YL951-YL968, YN231-YN236
2512Z			AL	0-0	44-21-26	D10527B			AJ	D12167P	PERS	1A		YN501-YR328
2513B	22	X2	AM	4-9	23-34-01	D10527B	B07			D12167P	27			YL951-YL968, YN231-YN236
2513B	22	X2	AM	4-9	44-21-26	D10527B	B07			D12167P	27			YN501-YR328
2513R	22	X2	AM	0-0	23-34-01	D10527B	A07			D12167P	26			YL951-YL968, YN231-YN236
2513R	22	X2	AM	0-0	44-21-26	D10527B	A07			D12167P	26			YN501-YR328
2513Z			AM	0-0	23-34-01	D10527B			AK	D12167P	PERS	1A		YL951-YL968, YN231-YN236
2513Z			AM	0-0	44-21-26	D10527B			AK	D12167P	PERS	1A		YN501-YR328
2514B	22	X2	AN	4-9	23-34-01	D10527B	D07			D12167P	29			YL951-YL968, YN231-YN236
2514B	22	X2	AN	4-9	44-21-26	D10527B	D07			D12167P	29			YN501-YR328
2514R	22	X2	AN	0-0	23-34-01	D10527B	C07			D12167P	28			YL951-YL968, YN231-YN236
2514R	22	X2	AN	0-0	44-21-26	D10527B	C07			D12167P	28			YN501-YR328
2514Z			AN	0-0	23-34-01	D10527B			AK	D12167P	PERS	1A		YL951-YL968, YN231-YN236
2514Z			AN	0-0	44-21-26	D10527B			AK	D12167P	PERS	1A		YN501-YR328
2515B	22	X2	AP	4-9	23-34-01	D10527B	B08			D12167P	31			YL951-YL968, YN231-YN236
2515B	22	X2	AP	4-9	44-21-26	D10527B	B08			D12167P	31			YN501-YR328
2515R	22	X2	AP	0-0	23-34-01	D10527B	A08			D12167P	30			YL951-YL968, YN231-YN236

WIRE LIST

D280A108

91-21-11

Section W5110

Page 22

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5115	286A5115				AUDIO ENTERTAINMENT - E4-2 SHELF TO AUDIO INTEGRATION BRKT AB0410 -MAS (continued)										
2515R	22	X2	AP		0-0	44-21-26	D10527B	A08			D12167P	30			YN501-YR328
2515Z			AP		0-0	23-34-01	D10527B			AK	D12167P	PERS	1A		YL951-YL968, YN231-YN236
2515Z			AP		0-0	44-21-26	D10527B			AK	D12167P	PERS	1A		YN501-YR328
2516B	22	X2	AQ		4-9	23-34-01	D10527B	D08			D12167P	33			YL951-YL968, YN231-YN236
2516B	22	X2	AQ		4-9	44-21-26	D10527B	D08			D12167P	33			YN501-YR328
2516R	22	X2	AQ		0-0	23-34-01	D10527B	C08			D12167P	32			YL951-YL968, YN231-YN236
2516R	22	X2	AQ		0-0	44-21-26	D10527B	C08			D12167P	32			YN501-YR328
2516Z			AQ		0-0	23-34-01	D10527B	PERB			D12167P	PERS	1A		YL951-YL968, YN231-YN236
2516Z			AQ		0-0	44-21-26	D10527B	PERB			D12167P	PERS	1A		YN501-YR328
2517B	22	X2	AR		4-10	23-34-01	D10527B	B12			D12163P	2			YL951-YL968, YN231-YN236
2517B	22	X2	AR		4-10	44-21-26	D10527B	B12			D12163P	2			YN501-YR328
2517R	22	X2	AR		0-0	23-34-01	D10527B	A12			D12163P	1			YL951-YL968, YN231-YN236
2517Z			AR		0-0	23-34-01	D10527B	PERB			D12163P	PERS	1A		YN501-YR328
2517Z			AR		0-0	44-21-26	D10527B	PERB			D12163P	PERS	1A		YL951-YL968, YN231-YN236
2518B	22	X2	AS		4-10	23-34-01	D10527B	D12			D12163P	4			YN501-YR328
2518B	22	X2	AS		0-0	23-34-01	D10527B	C12			D12163P	3			YL951-YL968, YN231-YN236
2518R	22	X2	AS		0-0	44-21-26	D10527B	C12			D12163P	3			YN501-YR328
2518Z			AS		0-0	23-34-01	D10527B	PERB			D12163P	PERS	1A		YL951-YL968, YN231-YN236
2518Z			AS		0-0	44-21-26	D10527B	PERB			D12163P	PERS	1A		YN501-YR328
2519B	22	X2	AT		4-10	23-34-01	D10527B	B14			D12163P	6			YL951-YL968, YN231-YN236
2519B	22	X2	AT		4-10	44-21-26	D10527B	B14			D12163P	6			YN501-YR328
2519R	22	X2	AT		0-0	23-34-01	D10527B	A14			D12163P	5			YL951-YL968, YN231-YN236
2519R	22	X2	AT		0-0	44-21-26	D10527B	A14			D12163P	5			YN501-YR328
2519Z			AT		0-0	23-34-01	D10527B	PERB			D12163P	PERS	1A		YL951-YL968, YN231-YN236

WIRE LIST

D280A108

91-21-11

Section W5110

Page 23

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type
W5115	286A5115				AUDIO ENTERTAINMENT - E4-2 SHELF TO AUDIO INTEGRATION BRKT AB0410 -MAS (continued)										
2519Z				AT	0-0	44-21-26	D10527B				D12163P	PERS	1A	YN501-YR328	
2520B	22	X2		AU	4-10	23-34-01	D10527B				D12163P	10		YL951-YL968, YN231-YN236	
2520B	22	X2		AU	4-10	44-21-26	D10527B				D12163P	10		YN501-YR328	
2520R	22	X2		AU	0-0	23-34-01	D10527B				D12163P	9		YL951-YL968, YN231-YN236	
2520R	22	X2		AU	0-0	44-21-26	D10527B				D12163P	9		YN501-YR328	
2520Z				AU	0-0	23-34-01	D10527B				D12163P	PERS	1A	YL951-YL968, YN231-YN236	
2520Z				AU	0-0	44-21-26	D10527B				D12163P	PERS	1A	YN501-YR328	
2521B	22	X2		AV	4-10	23-34-01	D10527B				D12163P	12		YL951-YL968, YN231-YN236	
2521B	22	X2		AV	4-10	44-21-26	D10527B				D12163P	12		YN501-YR328	
2521R	22	X2		AV	0-0	23-34-01	D10527B				D12163P	11		YL951-YL968, YN231-YN236	
2521R	22	X2		AV	0-0	44-21-26	D10527B				D12163P	11		YN501-YR328	
2521Z				AV	0-0	23-34-01	D10527B				D12163P	PERS	1A	YL951-YL968, YN231-YN236	
2522B	22	X2		AW	4-10	44-21-26	D10527B				D12163P	PERS	1A	YN501-YR328	
2522B	22	X2		AW	4-10	23-34-01	D10527B				D12163P	14		YL951-YL968, YN231-YN236	
2522B	22	X2		AW	4-10	44-21-26	D10527B				D12163P	14		YN501-YR328	
2522R	22	X2		AW	0-0	23-34-01	D10527B				D12163P	13		YL951-YL968, YN231-YN236	
2522R	22	X2		AW	0-0	44-21-26	D10527B				D12163P	13		YN501-YR328	
2522Z				AW	0-0	23-34-01	D10527B				D12163P	PERS	1A	YL951-YL968, YN231-YN236	
2524B	22	X2		AY	4-10	44-21-26	D10527B				D12163P	PERS	1A	YN501-YR328	
2524B	22	X2		AY	4-10	23-34-01	D10527B				D12163P	30		YL951-YL968, YN231-YN236	
2524B	22	X2		AY	4-10	44-21-26	D10527B				D12163P	30		YN501-YR328	
2524R	22	X2		AY	0-0	23-34-01	D10527B				D12163P	29		YL951-YL968, YN231-YN236	
2524R	22	X2		AY	0-0	44-21-26	D10527B				D12163P	29		YN501-YR328	
2524Z				AY	0-0	23-34-01	D10527B				D12163P	PERS	1A	YL951-YL968, YN231-YN236	
2524Z				AY	0-0	44-21-26	D10527B				D12163P	PERS	1A	YN501-YR328	
2528B	24	OT		BC	4-11	23-34-02	D10527A				D12169P	10		YL951-YL968, YN231-YN236	

WIRE LIST

D280A108

91-21-11

Section W5110

Page 24

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To				Effectivity
Wire No.	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W5115	286A5115			AUDIO ENTERTAINMENT - E4-2 SHELF TO AUDIO INTEGRATION BRKT AB0410 -MAS (continued)											
2528B	24	OT	BC	4-11	44-21-26	D10527A	D12			D12169P	10			YN501-YR328	
2528W	24	OT	BC	0-0	23-34-02	D10527A	C12			D12169P	9			YL951-YL968, YN231-YN236	
2528W	24	OT	BC	0-0	44-21-26	D10527A	C12			D12169P	9			YN501-YR328	
2528Z			BC	0-0	23-34-02	D10527A	PERB			D12169P	PERS	1A	YL951-YL968, YN231-YN236		
2528Z	24	OT	BC	0-0	44-21-26	D10527A	PERB			D12169P	PERS	1A		YN501-YR328	
2529B			BD	4-11	23-34-02	D10527A	D13			D12169P	12			YL951-YL968, YN231-YN236	
2529B	24	OT	BD	4-11	44-21-26	D10527A	D13			D12169P	12			YN501-YR328	
2529W	24	OT	BD	0-0	23-34-02	D10527A	C13			D12169P	11			YL951-YL968, YN231-YN236	
2529W	24	OT	BD	0-0	44-21-26	D10527A	C13			D12169P	11			YN501-YR328	
2529Z			BD	0-0	23-34-02	D10527A	PERB			D12169P	PERS	1A	YL951-YL968, YN231-YN236		
2529Z	24	OT	BD	0-0	44-21-26	D10527A	PERB			D12169P	PERS	1A		YN501-YR328	
2531B			BF	4-11	23-34-02	D10527A	D08			D12169P	27			YL951-YL968, YN231-YN236	
2531B	24	OT	BF	4-11	44-21-26	D10527A	D08			D12169P	27			YN501-YR328	
2531W	24	OT	BF	0-0	23-34-02	D10527A	C08			D12169P	26			YL951-YL968, YN231-YN236	
2531W	24	OT	BF	0-0	44-21-26	D10527A	C08			D12169P	26			YN501-YR328	
2531Z			BF	0-0	23-34-02	D10527A	PERB			D12169P	PERS	1A	YL951-YL968, YN231-YN236		
2531Z	24	OT	BF	0-0	44-21-26	D10527A	PERB			D12169P	PERS	1A		YN501-YR328	
2532B			BG	4-11	23-34-02	D10527A	D09			D12169P	29			YL951-YL968, YN231-YN236	
2532B	24	OT	BG	4-11	44-21-26	D10527A	D09			D12169P	29			YN501-YR328	
2532W	24	OT	BG	0-0	23-34-02	D10527A	C09			D12169P	28			YL951-YL968, YN231-YN236	
2532W	24	OT	BG	0-0	44-21-26	D10527A	C09			D12169P	28			YN501-YR328	
2532Z			BG	0-0	23-34-02	D10527A	PERB			D12169P	PERS	1A	YL951-YL968, YN231-YN236		
2532Z	22	X2	BG	0-0	44-21-26	D10527A	PERB			D12169P	PERS	1A		YN501-YR328	
2534B			BI	4-11	23-34-02	D10527A	A12			D12169P	8			YL951-YL968, YN231-YN236	
2534B	22	X2	BI	4-11	44-21-26	D10527A	A12			D12169P	8			YN501-YR328	
2534R	22	X2	BI	0-0	23-34-02	D10527A	A13			D12169P	7			YL951-YL968, YN231-YN236	

WIRE LIST

D280A108

91-21-11

Section W5110

Page 25

Nov 12/2012



WIRE LIST

91-21-11

Section W5110

Page 26

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5115	286A5115				AUDIO ENTERTAINMENT - E4-2 SHELF TO AUDIO INTEGRATION BRKT AB0410 -MAS (continued)										
2538Z				BM	0-0	44-21-26	D10527A	PERB			D12171P	PERS	1A		YN501-YR328
2539B	24		OT	BN	5-0	23-34-02	D10527A	D10			D12171P	27			YL951-YL968, YN231-YN236
2539B	24		OT	BN	5-0	44-21-26	D10527A	D10			D12171P	27			YN501-YR328
2539W	24		OT	BN	0-0	23-34-02	D10527A	C10			D12171P	26			YL951-YL968, YN231-YN236
2539W	24		OT	BN	0-0	44-21-26	D10527A	C10			D12171P	26			YN501-YR328
2539Z				BN	0-0	23-34-02	D10527A	PERB			D12171P	PERS	1A		YL951-YL968, YN231-YN236
2539Z				BN	0-0	44-21-26	D10527A	PERB			D12171P	PERS	1A		YN501-YR328
2540B	24		OT	BP	5-0	23-34-02	D10527A	D11			D12171P	29			YL951-YL968, YN231-YN236
2540B	24		OT	BP	5-0	44-21-26	D10527A	D11			D12171P	29			YN501-YR328
2540W	24		OT	BP	0-0	23-34-02	D10527A	C11			D12171P	28			YL951-YL968, YN231-YN236
2540Z				BP	0-0	44-21-26	D10527A	PERB			D12171P	PERS	1A		YN501-YR328
2541B	22		X2	BQ	5-0	23-34-02	D10527A	A11			D12171P	25			YL951-YL968, YN231-YN236
2541B	22		X2	BQ	5-0	44-21-26	D10527A	A11			D12171P	25			YN501-YR328
2541R	22		X2	BQ	0-0	23-34-02	D10527A	A10			D12171P	24			YL951-YL968, YN231-YN236
2541R	22		X2	BQ	0-0	44-21-26	D10527A	A10			D12171P	24			YN501-YR328
2541Z				BQ	0-0	44-21-26	D10527A	PERB			D12171P	PERS	1A		YL951-YL968, YN231-YN236
3001B	22		PC	GA	4-10	23-34-01	D10527B	D10			D12163P	19			YN501-YR328
3001R	22		PC	GA	0-0	23-34-01	D10527B	D09			D12163P	18			YL951-YL968, YN231-YN236
3001Y	22		PC	GA	0-0	23-34-01	D10527B	D11			D12163P	20			YL951-YL968, YN231-YN236
3501B	22		X3	HA	5-1	23-34-02	D10527A	B07			D12211P	32			YL951-YL968, YN231-YN236
3501B	22		X3	HA	5-1	44-21-26	D10527A	B07			D12211P	32			YN501-YR328
3501R	22		X3	HA	0-0	23-34-02	D10527A	A07			D12211P	31			YL951-YL968, YN231-YN236

WIRE LIST

D280A108

91-21-11

Section W5110

Page 27

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W5115	286A5115				AUDIO ENTERTAINMENT - E4-2 SHELF TO AUDIO INTEGRATION BRKT AB0410 -MAS (continued)										
3501R	22	X3	HA	0-0	44-21-26	D10527A	A07			D12211P	31			YN501-YR328	
3501Y	22	X3	HA	0-0	23-34-02	D10527A	C07			D12211P	33			YL951-YL968, YN231-YN236	
3501Y	22	X3	HA	0-0	44-21-26	D10527A	C07			D12211P	33			YN501-YR328	
3501Z			HA	0-0	23-34-02	D10527A	PERB			D12211P	PERS	1A		YL951-YL968, YN231-YN236	
3501Z			HA	0-0	44-21-26	D10527A	PERB			D12211P	PERS	1A		YN501-YR328	
FRAG				0-0	23-34-01	D10527B			AG	D10527B	PERB			YL951-YL968, YN231-YN236	
FRAG				0-0	44-21-26	D10527B			AG	D10527B	PERB			YN501-YR328	
FRAH				0-0	23-34-01	D10527B			AH	D10527B	PERB			YL951-YL968, YN231-YN236	
FRAH				0-0	44-21-26	D10527B			AH	D10527B	PERB			YN501-YR328	
FRAI				0-0	23-34-01	D10527B			AI	D10527B	PERB			YL951-YL968, YN231-YN236	
FRAI				0-0	44-21-26	D10527B			AI	D10527B	PERB			YN501-YR328	
FRAJ				0-0	23-34-01	D10527B			AJ	D10527B	PERB			YL951-YL968, YN231-YN236	
FRAJ				0-0	44-21-26	D10527B			AJ	D10527B	PERB			YN501-YR328	
FRAK				0-0	23-34-01	D10527B			AK	D10527B	PERB			YL951-YL968, YN231-YN236	
FRAK				0-0	44-21-26	D10527B			AK	D10527B	PERB			YN501-YR328	
YAAA				0-0	23-34-02	D10527A	PERB			OAS0001				YL951-YL968, YN231-YN236	
YAAA				0-0	44-21-26	D10527A	PERB			OAS0001				YN501-YR328	
YAAB				0-0	23-34-02	D12169P	PERB			OAS0001				YL951-YL968, YN231-YN236	
YAAB				0-0	44-21-26	D12169P	PERB			OAS0001				YN501-YR328	
YAAC				0-0	23-34-02	D12171P	PERB			OAS0001				YL951-YL968, YN231-YN236	
YAAC				0-0	44-21-26	D12171P	PERB			OAS0001				YN501-YR328	
YAAD				0-0	23-34-01	D10527C	PERB			OAS0003				YL951-YL968, YN231-YN236	
YAAD				0-0	44-21-26	D10527C	PERB			OAS0003				YN501-YR328	
YAAE				0-0	23-34-01	D10527B	PERB			OAS0003				YL951-YL968, YN231-YN236	
YAAE				0-0	44-21-26	D10527B	PERB			OAS0003				YN501-YR328	
YAAF				0-0	23-34-01	OAS0003				OAS0002				YL951-YL968, YN231-YN236	

WIRE LIST

D280A108

91-21-11

Section W5110

Page 28

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To				Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W5115	286A5115				AUDIO ENTERTAINMENT - E4-2 SHELF TO AUDIO INTEGRATION BRKT AB0410 -MAS (continued)											
YAAF					0-0	44-21-26	OAS0003					OAS0002				YN501-YR328
YAAG					0-0	23-34-01	D12165P	PERB				OAS0002				YL951-YL968, YN231-YN236
YAAG					0-0	44-21-26	D12165P	PERB				OAS0002				YN501-YR328
YAAH					0-0	23-34-01	D12167P	PERB				OAS0002				YL951-YL968, YN231-YN236
YAAH					0-0	44-21-26	D12167P	PERB				OAS0002				YN501-YR328
YAAI					0-0	23-34-01	D12163P	PERB				OAS0002				YL951-YL968, YN231-YN236
YAAI					0-0	44-21-26	D12163P	PERB				OAS0002				YN501-YR328
YAAJ					0-0	23-34-01	OAS0003					GD00272	ST..	E		YL951-YL968, YN231-YN236
YAAJ					0-0	44-21-26	OAS0003					GD00272	ST..	E		YN501-YR328
YAAK					0-0	23-34-02	D12211P	PERB				OAS0001				YL951-YL956
YAAK					0-0	23-34-02	D12211P	PERB				OAS0002				YL957-YL968, YN231-YN236
YAAK					0-0	44-21-26	D12211P	PERB				OAS0002				YN501-YR328
W5117	286A5117				AUDIO ENTERTAINMENT - AUDIO INTEGRATION BRKT AB0410 TO BITE PNL STA984											
0001	20		PA		102-11	23-34-02	D12211J		2			D10587	8			YL951-YL999
0001	20		PA		83-8	23-34-02	D12211J		2			D10587	8			YN231-YN260
0001	20		PA		83-8	44-21-26	D12211J		2			D10587	8			YN501
0001	20		PA		102-11	44-21-26	D12211J		2			D10587	8			YR301-YR328
0002	20		PA		9-2	23-34-02	GD03736	AC..	1			D10587	6			YL951-YN260
0002	20		PA		9-2	44-21-26	GD03736	AC..	1			D10587	6			YN501-YR328
0003	20		PA		9-2	23-34-02	GD03736	ST..	1			D10587	11			YL951-YN260
0003	20		PA		9-2	44-21-26	GD03736	ST..	1			D10587	11			YN501-YR328
3501B	22	X3	HA		102-11	23-34-02	D12211J		32			D10587	2			YL951-YL999
3501B	22	X3	HA		83-8	23-34-02	D12211J		32			D10587	2			YN231-YN260
3501B	22	X3	HA		83-8	44-21-26	D12211J		32			D10587	2			YN501
3501B	22	X3	HA		102-11	44-21-26	D12211J		32			D10587	2			YR301-YR328
3501R	22	X3	HA		0-0	23-34-02	D12211J		31			D10587	1			YL951-YN260
3501R	22	X3	HA		0-0	44-21-26	D12211J		31			D10587	1			YN501-YR328
3501Y	22	X3	HA		0-0	23-34-02	D12211J		33			D10587	9			YL951-YN260
3501Y	22	X3	HA		0-0	44-21-26	D12211J		33			D10587	9			YN501-YR328
3501Z			HA		0-0	23-34-02	D12211J	PERS	1A			D10587	PERB			YL951-YN260
3501Z			HA		0-0	44-21-26	D12211J	PERS	1A			D10587	PERB			YN501-YR328
YAAA					0-0	23-34-02	D12211J	PERB				OAS0001				YL951-YN260
YAAA					0-0	44-21-26	D12211J	PERB				OAS0001				YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W5110

Page 29

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description	From				To				Effectivity	
	GA	CO	TY		Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip		Term
W5117	286A5117			AUDIO ENTERTAINMENT - AUDIO INTEGRATION BRKT AB0410 TO BITE PNL STA984 (continued)										
YAAB					0-0	23-34-02	D10587		PERB		OAS0001			YL951-YN260
YAAB					0-0	44-21-26	D10587		PERB		OAS0001			YN501-YR328

For training purposes only!

WIRE LIST

D280A108

91-21-11

Section W5110

Page 30 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5121	286A5121				EE INTER-RACK - RIGHT (E1-X TO E3-X)										
0001	22		PA		11-8	34-51-21	D45123J		1		D45125J		1		YC051-YD158, YL951-YR328
0002	22		PA		11-8	SPARE	D45123J		2		D45125J		2		YC051-YD157
0003	22		PA		11-8	34-51-41	D45123J		3		D45125J		3		YC051-YD158, YL951-YR328
0004	22		PA		27-6	34-51-41	D45121P		A01		D45125J		4		YC051-YD158, YL951-YR328
0005	24		B6		24-4	31-31-15	D45147P		A02		D45143J		1		YC051-YD158, YL951-YR328
0006	24		B6		24-4	31-31-15	D45147P		B02		D45143J		2		YC051-YD158, YL951-YR328
0009	22		PA		24-5	SPARE	D45123J		4		D45147P		A01		YD158, YL951-YR328
0010	22		PA		24-5	SPARE	D45123J		5		D45147P		B01		YD158, YL951-YR328
0011	22		PA		3-3	SPARE	D45127P		A01		D45121P		B01		YC051-YD157
0011	22		PA		25-0	SPARE	D45127P		A01		D45123J		2		YD158, YL951-YL959, YN231-YN235
0011	22		PA		25-1	SPARE	D45127P		A01		D45123J		2		YL963-YL999, YN236-YR328
0012	22		PA		3-3	27-32-21	D45121P		A02		D45127P		B01		YC051-YD158, YL951-YL959, YN231-YN235
0012	22		PA		3-4	27-32-21	D45121P		A02		D45127P		B01		YL963-YL999, YN236-YR328
0013	24		PK		25-0	SPARE	D45123J		7		D45127P		B03		YC051-YD158, YL951-YL959, YN231-YN235
0013	24		PK		25-1	SPARE	D45123J		7		D45127P		B03		YL963-YL999, YN236-YR328
0014	24		PK		28-10	31-31-17	D45127P		A02		D45125J		14		YC051-YD158, YL951-YL959, YN231-YN235
0014	24		PK		28-11	31-31-17	D45127P		A02		D45125J		14		YL963-YL999, YN236-YR328
0015	24		B6		25-0	22-11-14	D45123J		8		D45127P		B02		YC051-YD158, YL951-YL959, YN231-YN235
0015	24		B6		25-1	22-11-14	D45123J		8		D45127P		B02		YL963-YL999, YN236-YR328

WIRE LIST
D280A108

91-21-11
Section W5120
Page 1
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5121	286A5121			EE INTER-RACK - RIGHT (E1-X TO E3-X) (continued)										
0016	22		PA	3-3	34-57-21	D45127P	A03			D45121P	B02			YC051-YD158, YL951-YL959, YN231-YN235
0016	22		PA	3-4	34-57-21	D45127P	A03			D45121P	B02			YL963-YL999, YN236-YR328
0017	20		PA	11-8	SPARE	D45123J	9			D45125J	9			YC051-YD158, YL951-YR328
0018	22		CQ	11-8	22-11-18	D45123J	10			D45125J	10			YC051-YD158, YL951-YR328
0023	24		PK	26-8	SPARE	D43323P	B04			D45213J	B02			YD158
0028	22		CQ	24-5	SPARE	D45123J	52			D45147P	A06			YD158
0029	24		PK	23-7	31-62-41	D45123J	53			D45121P	A04			YD158, YL951-YR328
0030	22		PA	11-8	34-51-41	D45123J	15			D45125J	5			YL951-YR328
0038	24		PK	27-1	31-31-15	D45002J	3			D45102P	3			YL963-YL999, YN236-YR328
0039	24		PK	27-1	31-31-15	D45002J	4			D45102P	4			YL963-YL999, YN236-YR328
2001B	24		Y2	AA	23-8	34-31-21	D45123J	21		D45141P	B05			YC051-YD158, YL951-YR328
2001R	24		Y2	AA	0-0	34-31-21	D45123J	20		D45141P	A05			YC051-YD158, YL951-YR328
2001Z				AA	0-0	34-31-21	D45123J	S/R		D45141P	PERG	1F		YC051-YD158, YL951-YR328
2002B	24		Y2	AB	2-7	27-32-22	D45141P	B06		D45147P	B10			YC051-YD158, YL951-YR328
2002R	24		Y2	AB	0-0	27-32-22	D45141P	A06		D45147P	A10			YC051-YD158, YL951-YR328
2002Z				AB	0-0	27-32-22	D45141P	PERG	1F	D45147P	PERG	1F		YC051-YD158, YL951-YR328
2003B	24		Y2	AC	25-0	34-31-21	D45123J	25		D45127P	B10			YC051-YD158, YL951-YL959, YN231-YN235
2003B	24		Y2	AC	25-1	34-31-21	D45123J	25		D45127P	B10			YL963-YL999, YN236-YR328
2003R	24		Y2	AC	0-0	34-31-21	D45123J	24		D45127P	A10			YC051-YD158, YL951-YR328
2003Z				AC	0-0	34-31-21	D45123J	S/R		D45127P	PERG	1F		YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5120

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5121	286A5121				EE INTER-RACK - RIGHT (E1-X TO E3-X) (continued)										
2004B	24	Y2	AD		11-8	34-51-21	D45123J	27			D45125J	21			YC051-YD158, YL951-YR328
2004R	24	Y2	AD		0-0	34-51-21	D45123J	26			D45125J	20			YC051-YD158, YL951-YR328
2004Z			AD		0-0	34-51-21	D45123J	S/R			D45125J	S/R			YC051-YD158, YL951-YR328
2005B	24	Y2	AE		23-8	34-51-21	D45123J	29			D45141P	B07			YC051-YD158, YL951-YR328
2005R	24	Y2	AE		0-0	34-51-21	D45123J	28			D45141P	A07			YC051-YD158, YL951-YR328
2005Z			AE		0-0	34-51-21	D45123J	S/R			D45141P	PERG	1F		YC051-YD158, YL951-YR328
2006B	24	Y2	AF		23-8	34-51-21	D45123J	31			D45141P	B08			YC051-YD158, YL951-YR328
2006R	24	Y2	AF		0-0	34-51-21	D45123J	30			D45141P	A08			YC051-YD158, YL951-YR328
2006Z			AF		0-0	34-51-21	D45123J	S/R			D45141P	PERG	1F		YC051-YD158, YL951-YR328
2007B	24	Y2	AG		25-0	34-51-21	D45123J	33			D45127P	B11			YC051-YD158, YL951-YL959, YN231-YN235
2007B	24	Y2	AG		25-1	34-51-21	D45123J	33			D45127P	B11			YL963-YL999, YN236-YR328
2007R	24	Y2	AG		0-0	34-51-21	D45123J	32			D45127P	A11			YC051-YD158, YL951-YR328
2007Z			AG		0-0	34-51-21	D45123J	S/R			D45127P	PERG	1F		YC051-YD158, YL951-YR328
2008B	24	Y2	AH		23-8	31-62-22	D45123J	35			D45141P	B09			YC051-YD158, YL951-YR328
2008R	24	Y2	AH		0-0	31-62-22	D45123J	34			D45141P	A09			YC051-YD158, YL951-YR328
2008Z			AH		0-0	31-62-22	D45123J	S/R			D45141P	PERG	1F		YC051-YD158, YL951-YR328
2009B	24	Y2	AI		24-11	22-11-51	D45127P	B14			D45143J	23			YC051-YD158, YL951-YL959, YN231-YN235
2009B	24	Y2	AI		25-0	22-11-51	D45127P	B14			D45143J	23			YL963-YL999, YN236-YR328

WIRE LIST
D280A108

91-21-11
Section W5120
Page 3
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5121	286A5121			EE INTER-RACK - RIGHT (E1-X TO E3-X) (continued)											
2009R	24	Y2	AI		0-0	22-11-51	D45127P	A14			D45143J	22			YC051-YD158, YL951-YR328
2009Z			AI		0-0	22-11-51	D45127P	PERG	1F		D45143J	S/R			YC051-YD158, YL951-YR328
2010B	24	Y2	AJ		3-3	31-62-25	D45121P	B10			D45127P	B12			YC051-YD158, YL951-YL959, YN231-YN235
2010B	24	Y2	AJ		3-4	31-62-25	D45121P	B10			D45127P	B12			YL963-YL999, YN236-YR328
2010R	24	Y2	AJ		0-0	31-62-25	D45121P	A10			D45127P	A12			YC051-YD158, YL951-YR328
2010Z			AJ		0-0	31-62-25	D45121P	PERG	1F		D45127P	PERG	1F		YC051-YD158, YL951-YR328
2011B	24	Y2	AK		3-3	31-62-25	D45121P	B11			D45127P	B13			YC051-YD158, YL951-YL959, YN231-YN235
2011B	24	Y2	AK		3-4	31-62-25	D45121P	B11			D45127P	B13			YL963-YL999, YN236-YR328
2011R	24	Y2	AK		0-0	31-62-25	D45121P	A11			D45127P	A13			YC051-YD158, YL951-YR328
2011Z			AK		0-0	31-62-25	D45121P	PERG	1F		D45127P	PERG	1F		YC051-YD158, YL951-YR328
2012B	24	Y2	AL		11-11	31-62-25	D45121P	B12			D10175	4			YC051-YD158, YL951-YR328
2012R	24	Y2	AL		0-0	31-62-25	D45121P	A12			D10175	3			YC051-YD158, YL951-YR328
2012Z			AL		0-0	31-62-25	D45121P	PERG	1F		D10175	S/R			YC051-YD158, YL951-YR328
2013B	24	Y2	AM		23-7	31-62-25	D45123J	39			D45121P	B13			YC051-YD158, YL951-YR328
2013R	24	Y2	AM		0-0	31-62-25	D45123J	38			D45121P	A13			YC051-YD158, YL951-YR328
2013Z			AM		0-0	31-62-25	D45123J	S/R			D45121P	PERG	1F		YC051-YD158, YL951-YR328
2014B	24	Y2	AN		11-10	31-62-25	D11804	4			D45121P	B14			YC051-YD158, YL951-YR328
2014R	24	Y2	AN		0-0	31-62-25	D11804	3			D45121P	A14			YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5120

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5121	286A5121				EE INTER-RACK - RIGHT (E1-X TO E3-X) (continued)										
2014Z				AN	0-0	31-62-25	D11804	S/R			D45121P	PERG	1F		YC051-YD158, YL951-YR328
2015B	24	Y2	AO		11-10	31-62-25	D11804	8			D45121P	B15			YC051-YD158, YL951-YR328
2015R	24	Y2	AO		0-0	31-62-25	D11804	7			D45121P	A15			YC051-YD158, YL951-YR328
2015Z				AO	0-0	31-62-25	D11804	S/R			D45121P	PERG	1F		YC051-YD158, YL951-YR328
2016B	24	Y2	AP		11-8	34-55-21	D45125J	23			D45123J	41			YC051-YD158, YL951-YR328
2016R	24	Y2	AP		0-0	34-55-21	D45125J	22			D45123J	40			YC051-YD158, YL951-YR328
2016Z				AP	0-0	34-55-21	D45125J	S/R			D45123J	S/R			YC051-YD158, YL951-YR328
2017B	24	Y2	AQ		27-6	34-55-21	D45125J	25			D45121P	B16			YC051-YD158, YL951-YR328
2017R	24	Y2	AQ		0-0	34-55-21	D45125J	24			D45121P	A16			YC051-YD158, YL951-YR328
2017Z				AQ	0-0	34-55-21	D45125J	S/R			D45121P	PERG	1F		YC051-YD158, YL951-YR328
2018B	24	Y2	AR		2-7	27-32-22	D45141P	B16			D45147P	B12			YC051-YD158, YL951-YR328
2018R	24	Y2	AR		0-0	27-32-22	D45141P	A16			D45147P	A12			YC051-YD158, YL951-YR328
2018Z				AR	0-0	27-32-22	D45141P	PERG	1F		D45147P	PERG	1F		YC051-YD158, YL951-YR328
2019B	24	Y2	AS		25-0	34-33-21	D45123J	43			D45127P	B04			YC051-YD158, YL951-YL959, YN231-YN235
2019B	24	Y2	AS		25-1	34-33-21	D45123J	43			D45127P	B04			YL963-YL999, YN236-YR328
2019R	24	Y2	AS		0-0	34-33-21	D45123J	42			D45127P	A04			YC051-YD158, YL951-YR328
2019Z				AS	0-0	34-33-21	D45123J	S/R			D45127P	PERG	1F		YC051-YD158, YL951-YR328
2020B	24	Y2	AT		3-3	34-33-21	D45127P	B15			D45121P	B19			YC051-YD158, YL951-YL959, YN231-YN235

WIRE LIST
D280A108

91-21-11
Section W5120
Page 5
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5121	286A5121			EE INTER-RACK - RIGHT (E1-X TO E3-X) (continued)											
2020B	24	Y2	AT		3-4	34-33-21	D45127P	B15			D45121P	B19			YL963-YL999, YN236-YR328
2020R	24	Y2	AT		0-0	34-33-21	D45127P	A15			D45121P	A19			YC051-YD158, YL951-YR328
2020Z			AT		0-0	34-33-21	D45127P	PERG	1F		D45121P	PERG	1F		YC051-YD158, YL951-YR328
2021B	24	Y2	AU		23-7	34-57-21	D45123J	45			D45121P	B20			YC051-YD158, YL951-YR328
2021R	24	Y2	AU		0-0	34-57-21	D45123J	44			D45121P	A20			YC051-YD158, YL951-YR328
2021Z			AU		0-0	34-57-21	D45123J	S/R			D45121P	PERG	1F		YC051-YD158, YL951-YR328
2022B	24	Y2	AV		24-5	SPARE	D45147P	B13			D45123J	47			YD158, YL951-YR328
2022R	24	Y2	AV		0-0	SPARE	D45147P	A13			D45123J	46			YD158, YL951-YR328
2022Z			AV		0-0	SPARE	D45147P	PERG	1F		D45123J	S/R			YD158, YL951-YR328
2023B	24	Y2	AW		24-5	SPARE	D45147P	B14			D45123J	49			YD158, YL951-YR328
2023R	24	Y2	AW		0-0	SPARE	D45147P	A14			D45123J	48			YD158, YL951-YR328
2023Z			AW		0-0	SPARE	D45147P	PERG	1F		D45123J	S/R			YD158, YL951-YR328
2024B	24	Y2	AX		24-5	SPARE	D45147P	B15			D45123J	51			YD158, YL951-YR328
2024R	24	Y2	AX		0-0	SPARE	D45147P	A15			D45123J	50			YD158, YL951-YR328
2024Z			AX		0-0	SPARE	D45147P	PERG	1F		D45123J	S/R			YD158, YL951-YR328
2025B	24	Y2	AY		3-3	SPARE	D45127P	B19			D45141P	B15			YD158
2025B	24	Y2	AY		3-3	SPARE	D45141P	B15			D45127P	B19			YL951-YL959, YN231-YN235
2025B	24	Y2	AY		3-4	SPARE	D45141P	B15			D45127P	B19			YL963-YL999, YN236-YR328
2025R	24	Y2	AY		0-0	SPARE	D45127P	A19			D45141P	A15			YD158
2025R	24	Y2	AY		0-0	SPARE	D45141P	A15			D45127P	A19			YL951-YR328
2025Z			AY		0-0	SPARE	D45127P	PERG	1F		D45141P	PERG	1F		YD158
2025Z			AY		0-0	SPARE	D45141P	PERG	1F		D45127P	PERG	1F		YL951-YR328
2026B	24	Y2	AZ		23-7	73-24-21	D45123J	17			D45121P	B07			YC051-YD158, YL951-YR328
2026R	24	Y2	AZ		0-0	73-24-21	D45123J	16			D45121P	A07			YC051-YD158, YL951-YR328
2026Z			AZ		0-0	73-24-21	D45123J	S/R			D45121P	PERG	1F		YC051-YD158, YL951-YR328
2027B	24	Y2	BA		23-7	SPARE	D45123J	19			D45121P	B08			YC051-YC058
2027B	22	X2	BA		23-6	31-32-15	D45143J	38			D45121P	B08			YC059-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5120

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Description Fam FT-IN		Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W5121	286A5121			EE INTER-RACK - RIGHT (E1-X TO E3-X) (continued)											
2027R	24	Y2	BA	0-0	SPARE	D45123J	18				D45121P	A08			YC051-YC058
2027R	22	X2	BA	0-0	31-32-15	D45143J	37				D45121P	A08			YC059-YD158, YL951-YR328
2027Z			BA	0-0	SPARE	D45123J	S/R				D45121P	PERG	1F		YC051-YC058
2027Z			BA	0-0	31-32-15	D45143J	S/R				D45121P	PERG	1F		YC059-YD158, YL951-YR328
2028B	24	Y2	BB	3-3	34-33-21	D45127P	B20				D45121P	B09			YC051-YD158, YL951-YL959, YN231-YN235
2028B	24	Y2	BB	3-4	34-33-21	D45127P	B20				D45121P	B09			YL963-YL999, YN236-YR328
2028R	24	Y2	BB	0-0	34-33-21	D45127P	A20				D45121P	A09			YC051-YD158, YL951-YR328
2028Z			BB	0-0	34-33-21	D45127P	PERG	1F			D45121P	PERG	1F		YC051-YD158, YL951-YR328
2029B	24	Y2	BC	23-7	22-11-51	D45141P	B11				D45143J	11			YC051-YD158, YL951-YR328
2029R	24	Y2	BC	0-0	22-11-51	D45141P	A11				D45143J	10			YC051-YD158, YL951-YR328
2029Z			BC	0-0	22-11-51	D45141P	PERG	1F			D45143J	S/R			YC051-YD158, YL951-YR328
2030B	24	Y2	BD	23-7	22-11-51	D45141P	B12				D45143J	13			YC051-YD158, YL951-YR328
2030R	24	Y2	BD	0-0	22-11-51	D45141P	A12				D45143J	12			YC051-YD158, YL951-YR328
2030Z			BD	0-0	22-11-51	D45141P	PERG	1F			D45143J	S/R			YC051-YD158, YL951-YR328
2031B	24	Y2	BE	23-7	22-11-51	D45141P	B13				D45143J	15			YC051-YD158, YL951-YR328
2031R	24	Y2	BE	0-0	22-11-51	D45141P	A13				D45143J	14			YC051-YD158, YL951-YR328
2031Z			BE	0-0	22-11-51	D45141P	PERG	1F			D45143J	S/R			YC051-YD158, YL951-YR328
2032B	24	Y2	BF	24-11	22-11-51	D45127P	B09				D45143J	17			YC051-YD158, YL951-YL959, YN231-YN235
2032B	24	Y2	BF	25-0	22-11-51	D45127P	B09				D45143J	17			YL963-YL999, YN236-YR328

WIRE LIST
D280A108

91-21-11
Section W5120
Page 7
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W5121	286A5121				EE INTER-RACK - RIGHT (E1-X TO E3-X) (continued)										
2032R	24	Y2	BF		0-0	22-11-51	D45127P	A09			D45143J	16		YC051-YD158, YL951-YR328	
2032Z			BF		0-0	22-11-51	D45127P	PERG	1F		D45143J	S/R		YC051-YD158, YL951-YR328	
2033B	24	Y2	BG		3-3	77-31-21	D45127P	B05			D45121P	B05		YC051-YD158, YL951-YL959, YN231-YN235	
2033B	24	Y2	BG		3-4	77-31-21	D45127P	B05			D45121P	B05		YL963-YL999, YN236-YR328	
2033R	24	Y2	BG		0-0	77-31-21	D45127P	A05			D45121P	A05		YC051-YD158, YL951-YR328	
2033Z			BG		0-0	77-31-21	D45127P	PERG	1F		D45121P	PERG	1F	YC051-YD158, YL951-YR328	
2034B	24	Y2	BH		3-3	77-31-21	D45127P	B06			D45121P	B06		YC051-YD158, YL951-YL959, YN231-YN235	
2034B	24	Y2	BH		3-4	77-31-21	D45127P	B06			D45121P	B06		YL963-YL999, YN236-YR328	
2034R	24	Y2	BH		0-0	77-31-21	D45127P	A06			D45121P	A06		YC051-YD158, YL951-YR328	
2034Z			BH		0-0	77-31-21	D45127P	PERG	1F		D45121P	PERG	1F	YC051-YD158, YL951-YR328	
2035B	24	Y2	BJ		28-10	34-55-21	D45127P	B07			D45125J	27		YC051-YD158, YL951-YL959, YN231-YN235	
2035B	24	Y2	BJ		28-11	34-55-21	D45127P	B07			D45125J	27		YL963-YL999, YN236-YR328	
2035R	24	Y2	BJ		0-0	34-55-21	D45127P	A07			D45125J	26		YC051-YD158, YL951-YR328	
2035Z			BJ		0-0	34-55-21	D45127P	PERG	1F		D45125J	S/R		YC051-YD158, YL951-YR328	
2036B	24	Y2	BK		3-3	34-41-11	D45127P	B08			D45141P	B14		YC051-YD158, YL951-YL959, YN231-YN235	
2036B	24	Y2	BK		3-4	34-41-11	D45127P	B08			D45141P	B14		YL963-YL999, YN236-YR328	
2036R	24	Y2	BK		0-0	34-41-11	D45127P	A08			D45141P	A14		YC051-YD158, YL951-YR328	

WIRE LIST

D280A108

91-21-11

Section W5120

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Description Fam FT-IN		Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W5121	286A5121			EE INTER-RACK - RIGHT (E1-X TO E3-X) (continued)											
2036Z				BK	0-0	34-41-11	D45127P	PERG	1F		D45141P	PERG	1F		YC051-YD158, YL951-YR328
2037B	24	Y2	BL		11-6	22-11-51	D45143J		19		D45125J		29		YC051-YD158, YL951-YR328
2037R	24	Y2	BL		0-0	22-11-51	D45143J		18		D45125J		28		YC051-YD158, YL951-YR328
2037Z				BL	0-0	22-11-51	D45143J		S/R		D45125J		S/R		YC051-YD158, YL951-YR328
2038B	24	Y2	BM		11-8	34-51-21	D45123J		55		D45125J		31		YC051-YD158, YL951-YR328
2038R	24	Y2	BM		0-0	34-51-21	D45123J		54		D45125J		30		YC051-YD158, YL951-YR328
2038Z				BM	0-0	34-51-21	D45123J		S/R		D45125J		S/R		YC051-YD158, YL951-YR328
2039B	24	Y2	BN		11-6	34-31-21	D45143J		21		D45125J		33		YC051-YD158, YL951-YR328
2039R	24	Y2	BN		0-0	34-31-21	D45143J		20		D45125J		32		YC051-YD158, YL951-YR328
2039Z				BN	0-0	34-31-21	D45143J		S/R		D45125J		S/R		YC051-YD158, YL951-YR328
2040B	22	X2	BO		3-3	78-36-21	D45121P		B17		D45127P		B17		YC051-YD158, YL951-YL959, YN231-YN235
2040B	22	X2	BO		3-4	78-36-21	D45121P		B17		D45127P		B17		YL963-YL999, YN236-YR328
2040R	22	X2	BO		0-0	78-36-21	D45121P		A17		D45127P		A17		YC051-YD158, YL951-YR328
2040Z				BO	0-0	78-36-21	D45121P	PERG	1F		D45127P	PERG	1F		YC051-YD158, YL951-YR328
2041B	22	X2	BP		3-3	78-36-21	D45121P		B18		D45127P		B18		YC051-YD158, YL951-YL959, YN231-YN235
2041B	22	X2	BP		3-4	78-36-21	D45121P		B18		D45127P		B18		YL963-YL999, YN236-YR328
2041R	22	X2	BP		0-0	78-36-21	D45121P		A18		D45127P		A18		YC051-YD158, YL951-YR328
2041Z				BP	0-0	78-36-21	D45121P	PERG	1F		D45127P	PERG	1F		YC051-YD158, YL951-YR328
2042B	24	Y2	BQ		4-6	31-62-25	D45141P		B17		D43323P		B06		YC051-YD157

WIRE LIST
D280A108

91-21-11
Section W5120
Page 9
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5121	286A5121			EE INTER-RACK - RIGHT (E1-X TO E3-X) (continued)											
2042B	24	Y2	BQ		3-4	31-62-25	D45141P	B17			D43323P	B06			YD158, YL951-YN260
2042R	24	Y2	BQ		0-0	31-62-25	D45141P	A17			D43323P	A06			YC051-YD158, YL951-YN260
2042Z			BQ		0-0	31-62-25	D45141P	PERG	1F		D43323P	PERG	1F		YC051-YD158, YL951-YN260
2043B	24	Y2	BR		27-9	34-61-23	D43323P	B07			D45213J	B10			YC051-YD157
2043B	24	Y2	BR		26-8	34-61-23	D43323P	B07			D45213J	B10			YD158, YL951-YL959, YN231-YN235
2043B	24	Y2	BR		26-10	34-61-23	D43323P	B07			D45213J	B10			YL963-YL999, YN236-YR328
2043R	24	Y2	BR		0-0	34-61-23	D43323P	A07			D45213J	A10			YC051-YD158, YL951-YR328
2043Z			BR		0-0	34-61-23	D43323P	PERG	1F		D45213J	PERG	1F		YC051-YD158, YL951-YR328
2044B	24	Y2	BS		25-11	SPARE	D45213J	B11			D45147P	B11			YC051-YD157
2044R	24	Y2	BS		0-0	SPARE	D45213J	A11			D45147P	A11			YC051-YD157
2044Z			BS		0-0	SPARE	D45213J	PERG	1F		D45147P	PERG	1F		YC051-YD157
2045B	24	Y2	BT		3-11	34-61-23	D43323P	B08			D45147P	B09			YC051-YD157
2045B	24	Y2	BT		2-10	34-61-23	D43323P	B08			D45147P	B09			YD158, YL951-YR328
2045R	24	Y2	BT		0-0	34-61-23	D43323P	A08			D45147P	A09			YC051-YD158, YL951-YR328
2045Z			BT		0-0	34-61-23	D43323P	PERG	1F		D45147P	PERG	1F		YC051-YD158, YL951-YR328
2049B	24	Y2	BY		27-9	34-61-21	D43323P	B05			D45213J	B09			YC051-YD157
2049B	24	Y2	BY		26-8	34-61-21	D43323P	B05			D45213J	B09			YD158, YL951-YL959, YN231-YN235
2049B	24	Y2	BY		26-10	34-61-21	D43323P	B05			D45213J	B09			YL963-YL999, YN236-YR328
2049R	24	Y2	BY		0-0	34-61-21	D43323P	A05			D45213J	A09			YC051-YD158, YL951-YR328
2049Z			BY		0-0	34-61-21	D43323P	PERG	1F		D45213J	PERG	1F		YC051-YD158, YL951-YR328
2051B	24	Y2	CA		3-4	SPARE	D43323P	B10			D45141P	B10			YD158
2051R	24	Y2	CA		0-0	SPARE	D43323P	A10			D45141P	A10			YD158
2051Z			CA		0-0	SPARE	D43323P	PERG	1F		D45141P	PERG	1F		YD158
2053B	24	Y2	CC		26-8	34-61-25	D45213J	B03			D43323P	B01			YD158, YL951-YL959, YN231-YN235
2053B	24	Y2	CC		26-10	34-61-25	D45213J	B03			D43323P	B01			YL963-YL999, YN236-YN260

WIRE LIST

D280A108

91-21-11

Section W5120

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5121	286A5121				EE INTER-RACK - RIGHT (E1-X TO E3-X) (continued)										
2053R	24	Y2	CC		0-0	34-61-25	D45213J	A03			D43323P	A01			YD158, YL951-YN260
2053Z			CC		0-0	34-61-25	D45213J	PERG	1F		D43323P	PERG	1F		YD158, YL951-YN260
2054B	24	Y2	CD		26-8	34-61-25	D45213J	B04			D43323P	B02			YD158, YL951-YL959, YN231-YN235
2054B	24	Y2	CD		26-10	34-61-25	D45213J	B04			D43323P	B02			YL963-YL999, YN236-YN260
2054R	24	Y2	CD		0-0	34-61-25	D45213J	A04			D43323P	A02			YD158, YL951-YN260
2054Z			CD		0-0	34-61-25	D45213J	PERG	1F		D43323P	PERG	1F		YD158, YL951-YN260
2055B	24	Y2	CE		26-8	34-61-25	D45213J	B05			D43323P	B03			YD158, YL951-YL959, YN231-YN235
2055B	24	Y2	CE		26-10	34-61-25	D45213J	B05			D43323P	B03			YL963-YL999, YN236-YN260
2055R	24	Y2	CE		0-0	34-61-25	D45213J	A05			D43323P	A03			YD158, YL951-YN260
2055Z			CE		0-0	34-61-25	D45213J	PERG	1F		D43323P	PERG	1F		YD158, YL951-YN260
2056B	24	Y2	CF		2-10	SPARE	D43323P	B17			D45147P	B17			YD158
2056R	24	Y2	CF		0-0	SPARE	D43323P	A17			D45147P	A17			YD158
2056Z			CF		0-0	SPARE	D43323P	PERG	1F		D45147P	PERG	1F		YD158
2057B	24	Y2	CG		26-8	SPARE	D43323P	B12			D45213J	B12			YD158
2057R	24	Y2	CG		0-0	SPARE	D43323P	A12			D45213J	A12			YD158
2057Z			CG		0-0	SPARE	D43323P	PERG	1F		D45213J	PERG	1F		YD158
2058B	24	Y2	CH		26-8	SPARE	D43323P	B13			D45213J	B13			YD158
2058R	24	Y2	CH		0-0	SPARE	D43323P	A13			D45213J	A13			YD158
2058Z			CH		0-0	SPARE	D43323P	PERG	1F		D45213J	PERG	1F		YD158
2059B	24	Y2	CI		2-10	23-27-33	D43323P	B18			D45147P	B18			YD158, YL951-YR328
2059R	24	Y2	CI		0-0	23-27-33	D43323P	A18			D45147P	A18			YD158, YL951-YR328
2059Z			CI		0-0	23-27-33	D43323P	PERG	1F		D45147P	PERG	1F		YD158, YL951-YR328
2060B	24	Y2	CJ		26-8	23-27-33	D43323P	B14			D45213J	B14			YD158, YL951-YL959, YN231-YN235
2060B	24	Y2	CJ		26-10	23-27-33	D43323P	B14			D45213J	B14			YL963-YL999, YN236-YR328
2060R	24	Y2	CJ		0-0	23-27-33	D43323P	A14			D45213J	A14			YD158, YL951-YR328
2060Z			CJ		0-0	23-27-33	D43323P	PERG	1F		D45213J	PERG	1F		YD158, YL951-YR328
2061B	24	Y2	CK		26-8	23-27-33	D43323P	B15			D45213J	B15			YD158, YL951-YL959, YN231-YN235
2061B	24	Y2	CK		26-10	23-27-33	D43323P	B15			D45213J	B15			YL963-YL999, YN236-YN260
2061R	24	Y2	CK		0-0	23-27-33	D43323P	A15			D45213J	A15			YD158, YL951-YN260
2061Z			CK		0-0	23-27-33	D43323P	PERG	1F		D45213J	PERG	1F		YD158, YL951-YN260
2063B	24	Y2	CM		3-4	SPARE	D43323P	B11			D45141P	B20			YD158

WIRE LIST

D280A108

91-21-11

Section W5120

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5121		286A5121					EE INTER-RACK - RIGHT (E1-X TO E3-X) (continued)									
2063R		24		Y2	CM	0-0	SPARE	D43323P	A11			D45141P	A20			YD158
2063Z					CM	0-0	SPARE	D43323P	PERG	1F		D45141P	PERG	1F		YD158
2064B		24		Y2	CN	26-8	SPARE	D43323P	B16			D45213J	B16			YD158
2064R		24		Y2	CN	0-0	SPARE	D43323P	A16			D45213J	A16			YD158
2064Z					CN	0-0	SPARE	D43323P	PERG	1F		D45213J	PERG	1F		YD158
2065B		24		Y2	CP	2-10	SPARE	D43323P	B20			D45147P	B20			YD158
2065R		24		Y2	CP	0-0	SPARE	D43323P	A20			D45147P	A20			YD158
2065Z					CP	0-0	SPARE	D43323P	PERG	1F		D45147P	PERG	1F		YD158
2066B		24		Y2	CQ	2-7	SPARE	D45141P	B03			D45147P	B03			YD158
2066B		24		Y2	CQ	2-7	31-62-25	D45141P	B03			D45147P	B03			YL951-YR328
2066R		24		Y2	CQ	0-0	SPARE	D45141P	A03			D45147P	A03			YD158
2066R		24		Y2	CQ	0-0	31-62-25	D45141P	A03			D45147P	A03			YL951-YR328
2066Z					CQ	0-0	SPARE	D45141P	PERG	1F		D45147P	PERG	1F		YD158
2066Z					CQ	0-0	31-62-25	D45141P	PERG	1F		D45147P	PERG	1F		YL951-YR328
2067B		24		Y2	CR	2-7	SPARE	D45141P	B04			D45147P	B04			YD158
2067B		24		Y2	CR	2-7	31-62-25	D45141P	B04			D45147P	B04			YL951-YR328
2067R		24		Y2	CR	0-0	SPARE	D45141P	A04			D45147P	A04			YD158
2067R		24		Y2	CR	0-0	31-62-25	D45141P	A04			D45147P	A04			YL951-YR328
2067Z					CR	0-0	SPARE	D45141P	PERG	1F		D45147P	PERG	1F		YD158
2067Z					CR	0-0	31-62-25	D45141P	PERG	1F		D45147P	PERG	1F		YL951-YR328
2070B		24		Y2	BI	2-7	SPARE	D45121P	B03			D45147P	B05			YD158, YL951-YR328
2070R		24		Y2	BI	0-0	SPARE	D45121P	A03			D45147P	A05			YD158, YL951-YR328
2070Z					BI	0-0	SPARE	D45121P	PERG	1F		D45147P	PERG	1F		YD158, YL951-YR328
2072B		24		Y2	DS	29-0	34-45-21	D45125J	19			D43323P	B09			YD158
2072R		24		Y2	DS	0-0	34-45-21	D45125J	18			D43323P	A09			YD158
2072Z					DS	0-0	34-45-21	D45125J	S/R			D43323P	PERG	1F		YD158
2084B		24		Y2	CS	2-7	SPARE	D45141P	B01			D45147P	B11			YD158, YL951-YR328
2084R		24		Y2	CS	0-0	SPARE	D45141P	A01			D45147P	A11			YD158, YL951-YR328
2084Z					CS	0-0	SPARE	D45141P	PERG	1F		D45147P	PERG	1F		YD158, YL951-YR328
2086B		24		Y2	CU	2-7	SPARE	D45141P	B02			D45147P	B16			YD158, YL951-YR328
2086R		24		Y2	CU	0-0	SPARE	D45141P	A02			D45147P	A16			YD158, YL951-YR328
2086Z					CU	0-0	SPARE	D45141P	PERG	1F		D45147P	PERG	1F		YD158, YL951-YR328
2100B		24		Y2	BX	26-4	31-35-04	D43263P	B13			D41563P	B05			YL963-YL999, YN236-YR328
2100R		24		Y2	BX	0-0	31-35-04	D43263P	A13			D41563P	A05			YL963-YL999, YN236-YR328
2100Z					BX	0-0	31-35-04	D43263P	PERG	1F		D41563P	PERG	1F		YL963-YL999, YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W5120

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY	Description Fam FT-IN Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W5121	286A5121	EE INTER-RACK - RIGHT (E1-X TO E3-X) (continued)									
2516B	24	Y2 YZ	27-1	31-31-13	D45102P	2	D45002J	2			YL963-YL999, YN236-YR328
2516R	24	Y2 YZ	0-0	31-31-13	D45102P	1	D45002J	1			YL963-YL999, YN236-YR328
2516Z		YZ	0-0	31-31-13	D45102P	S/R	D45002J	S/R			YL963-YL999, YN236-YR328
2668B	24	Y2 GS	28-10	SPARE	D45127P	B16	D45125J	42			YD158, YL951-YL959, YN231-YN235
2668B	24	Y2 GS	28-11	SPARE	D45127P	B16	D45125J	42			YL963-YL999, YN236-YR328
2668R	24	Y2 GS	0-0	SPARE	D45127P	A16	D45125J	41			YD158, YL951-YR328
2668Z		GS	0-0	SPARE	D45127P	PERG 1F	D45125J	S/R			YD158, YL951-YR328
W5122	286A5122	P91 TO TB1802, TB1804, & TB5180									
0541	18	CQ	21-6	24-52-11	D11416	41	TB5180C	3	E		YC051-YD158
0541	18	CQ	21-11	24-52-11	D11416	41	TB5180C	3	E		YD160-YR328
0542	18	CQ	21-5	24-52-11	D11416	42	TB5180C	2	E		YC051-YD158
0542	18	CQ	21-10	24-52-11	D11416	42	TB5180C	2	E		YD160-YR328
0543	18	CQ	21-5	24-52-11	D11416	43	TB5180C	1	E		YC051-YD158
0543	18	CQ	21-10	24-52-11	D11416	43	TB5180C	1	E		YD160-YR328
5501	22	CQ	18-10	21-27-31	D48126P	A01	SP02002		S		YC051-YD158
5501	22	CQ	18-9	21-27-31	D48126P	A01	SP02002		S		YD160-YR328
5507	24	PK	18-6	21-42-11	D11416	7	D48126P	A04			YC051-YD158
5507	24	PK	18-11	21-42-11	D11416	7	D48126P	A04			YD160-YR328
5508	22	CQ	18-6	21-27-31	D11416	8	D48126P	A02			YC051-YD158
5508	22	CQ	18-11	21-27-31	D11416	8	D48126P	A02			YD160-YR328
W5124	286A5124	AB0727 TO J11 (WITH E6)									
0508	20	PA	46-9	27-31-11	SP00503	S	D46616P	1			YC054-YC058
0508	20	PA	47-5	27-31-11	SP00503	S	D46616P	1			YC059-YL999, YR301-YR328
0508	20	PA	38-1	27-31-11	SP00503	S	D46616P	1			YN231-YN501
0509	20	PA	46-9	27-31-11	SP00505	S	D46616P	2			YC054-YC058
0509	20	PA	47-5	27-31-11	SP00505	S	D46616P	2			YC059-YL999, YR301-YR328
0509	20	PA	38-1	27-31-11	SP00505	S	D46616P	2			YN231-YN501
0510	20	PA	6-1	27-31-11	D46616P	3	GD00431	DC..	1		YC054-YC058
0510	20	PA	6-3	27-31-11	D46616P	3	GD00431	DC..	1		YC059-YR328
0511	20	GK	48-0	27-31-37	SP00536	S	D46616P	5			YC051-YC057

WIRE LIST

D280A108

91-21-11

Section W5120

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5124		286A5124			AB0727 TO J11 (WITH E6) (continued)											
0511		24		PK		46-9	27-31-37	SP00536		S		D46616P	5			YC058
0511		24		PK		47-5	27-31-37	SP00536		S		D46616P	5			YC059-YL999, YR301-YR328
0511		24		PK		38-1	27-31-37	SP00536		S		D46616P	5			YN231-YN501
0512		20		PA		48-0	27-31-37	SP00538		S		D46616P	6			YC051-YC057
0512		20		PA		46-9	27-31-37	SP00538		S		D46616P	6			YC058
0512		20		PA		47-5	27-31-37	SP00538		S		D46616P	6			YC059-YL999, YR301-YR328
0512		20		PA		38-1	27-31-37	SP00538		S		D46616P	6			YN231-YN501
0513		20		GK		2-0	27-31-37	SM00001		S		D46616P	7			YC051-YC057
0513		24		PK		0-7	27-31-37	SM00001		S		D46616P	7			YC058-YD158
0513		24		PK		1-7	27-31-37	SM00001		S		D46616P	7			YD160-YR328
0514		20		GK		48-0	27-31-37	SP00540		S		SM00001		S		YC051-YC057
0514		24		PK		46-9	27-31-37	SP00540		S		SM00001		S		YC058
0514		24		PK		47-5	27-31-37	SP00540		S		SM00001		S		YC059-YD158
0514		24		PK		46-5	27-31-37	SP00540		S		SM00001		S		YD160-YL999, YR301-YR328
0514		24		PK		37-0	27-31-37	SP00540		S		SM00001		S		YN231-YN501
0515		20		PA		7-0	27-31-37	SM00001		S		GD00431	DC..	1		YC051-YC057
0515		22		PA		6-1	27-31-37	SM00001		S		GD00431	DC..	1		YC058
0515		22		PA		6-3	27-31-37	SM00001		S		GD00431	DC..	1		YC059-YD158
0515		22		PA		4-9	27-31-37	SM00001		S		GD00431	DC..	1		YD160-YR328
0516		20		PA		48-0	27-31-37	D46616P	4			SP00542		S		YC051-YC057
0516		20		PA		46-9	27-31-37	D46616P	4			SP00542		S		YC058
0516		20		PA		47-5	27-31-37	D46616P	4			SP00542		S		YC059-YL999, YR301-YR328
0516		20		PA		38-1	27-31-37	D46616P	4			SP00542		S		YN231-YN501
0517		20		PA		59-8	27-41-12	SP00170		S		D46616P	23			YC059-YL999, YR301-YR328
0517		20		PA		49-6	27-41-12	SP00170		S		D46616P	23			YN231-YN501
0518		18		PA		59-8	27-41-12	SP00372		S		D46616P	22			YC059-YL999, YR301-YR328
0518		18		PA		49-6	27-41-12	SP00372		S		D46616P	22			YN231-YN501
0519		20		PA		59-8	27-41-12	SP00374		S		D46616P	24			YC059-YL999, YR301-YR328
0519		20		PA		49-6	27-41-12	SP00374		S		D46616P	24			YN231-YN501
0520		20		PA		59-8	27-41-12	SP00110		S		D46616P	25			YC059-YL999, YR301-YR328
0520		20		PA		49-6	27-41-12	SP00110		S		D46616P	25			YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W5120

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W5124	286A5124				AB0727 TO J11 (WITH E6) (continued)											
0521	20		PA		59-8		27-41-12	SP00376		S		D46616P	21			YC059-YL999, YR301-YR328
0521	20		PA		49-6		27-41-12	SP00376		S		D46616P	21			YN231-YN501
0522	18		PA		59-8		27-41-12	SP00114		S		D46616P	20			YC059-YL999, YR301-YR328
0522	18		PA		49-6		27-41-12	SP00114		S		D46616P	20			YN231-YN501
0523	20		PA		59-8		27-41-12	SP00124		S		D46616P	17			YC059-YL999, YR301-YR328
0523	20		PA		49-6		27-41-12	SP00124		S		D46616P	17			YN231-YN501
0524	20		PA		59-8		27-41-12	SP00368		S		D46616P	18			YC059-YL999, YR301-YR328
0524	20		PA		49-6		27-41-12	SP00368		S		D46616P	18			YN231-YN501
0525	20		PA		59-8		27-41-12	SP00370		S		D46616P	19			YC059-YL999, YR301-YR328
0525	20		PA		49-6		27-41-12	SP00370		S		D46616P	19			YN231-YN501
0526	20		PA		8-4		27-41-12	D46616P	13			GD00654	DC..	1		YC059-YR328
0529	22		PA		57-2		29-25-11	D46602J	5			D46618P	5			YC051-YL999, YR301-YR328
0529	22		PA		47-0		29-25-11	D46602J	5			D46618P	5			YN231-YN501
0530	18		PA		57-2		29-25-11	D46602J	6			D46618P	6			YC051-YL999, YR301-YR328
0530	18		PA		47-0		29-25-11	D46602J	6			D46618P	6			YN231-YN501
0531	18		PA		57-2		29-25-11	D46602J	7			D46618P	7			YC051-YL999, YR301-YR328
0531	18		PA		47-0		29-25-11	D46602J	7			D46618P	7			YN231-YN501
0532	18		HL		26-2		27-31-11	SP00092		S		D46618P	15			YC051-YC053
0533	18		HL		26-2		27-31-11	SP00094		S		D46618P	16			YC051-YC053
0534	20		PA		7-11		27-31-11	D46618P	14			GD00654	DC..	1		YC051-YC053
0535	18		PA		57-2		29-25-11	D46602J	8			D46618P	8			YC051-YL999, YR301-YR328
0535	18		PA		47-0		29-25-11	D46602J	8			D46618P	8			YN231-YN501
0536	18		PA		57-2		29-25-11	D46602J	9			D46618P	9			YC051-YL999, YR301-YR328
0536	18		PA		47-0		29-25-11	D46602J	9			D46618P	9			YN231-YN501
0545	20		PA		28-0		33-26-31	D46616P	10			D07106P	=1	VG		YR315-YR328
0546	20		PA		26-8		33-26-31	D46616P	9			D07108P	=1	VR		YR315-YR328
0547	20		PA		26-8		33-26-31	D46616P	8			D07164P	=1	VG		YR315-YR328
0548	20		PA		8-4		33-26-31	D46616P	11			GD00654	AC..	1		YR315-YR328

WIRE LIST

D280A108

91-21-11

Section W5120

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5124		286A5124			AB0727 TO J11 (WITH E6) (continued)											
0566		18		PA		57-2	29-25-11	D46602J	1			D46618P	1			YC051-YL999, YR301-YR328
0566		18		PA		47-0	29-25-11	D46602J	1			D46618P	1			YN231-YN501
0567		18		PA		57-2	29-25-11	D46602J	2			D46618P	2			YC051-YL999, YR301-YR328
0567		18		PA		47-0	29-25-11	D46602J	2			D46618P	2			YN231-YN501
0568		18		PA		57-2	29-25-11	D46602J	3			D46618P	3			YC051-YL999, YR301-YR328
0568		18		PA		47-0	29-25-11	D46602J	3			D46618P	3			YN231-YN501
0569		18		PA		46-8	29-25-11	SP00634		S		D46618P	4			YC051-YL999, YR301-YR328
0569		18		PA		37-3	29-25-11	SP00634		S		D46618P	4			YN231-YN501
0570		20		PA		6-0	29-25-11	D46618P	10			GD00431	DC..	1		ALL
0571		20		PA		6-0	29-25-11	D46618P	11			GD00431	DC..	1		ALL

WIRE LIST

D280A108

91-21-11

Section W5120

Page 16 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5134	286A5134			DISC AB0500DL TO E2-2											
0503	22		PA		30-2	27-23-14	D43008P	A01			D40312J	1			YC051-YL999, YR301-YR328
0503	22		PA		20-10	27-23-14	D43008P	A01			D40312J	1			YN231-YN501
0568	20		PA		1-0	29-25-11	D43008P	B03			SM00002		S		ALL
0570	18		PA		30-2	29-25-11	SM00002		S		D40312J	10			YC051-YL999, YR301-YR328
0570	18		PA		20-4	29-25-11	SM00002		S		D40312J	10			YN231-YN501
W5137	286A5137			VOR ANTENNA LEFT - RF PWR DIV-1 TO R315 LOC ANTENNA SWITCH RELAY-1											
001CO				AA	0-0	34-31-11	D02113	=C1			D03779	=C1			ALL
001CX			0F	AA	1-8	34-31-11	D02113	=A1			D03779	=A1			ALL
W5139	286A5139			VOR ANTENNA RIGHT - RF PWR DIV-2 TO R316 LOC ANTENNA SWITCH RELAY-2											
001CO				AA	0-0	34-31-21	D02121	=C1			D03785	=C1			ALL
001CX			0F	AA	1-9	34-31-21	D02121	=A1			D03785	=A1			ALL

WIRE LIST

D280A108

91-21-11

Section W5130

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To				
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5142	286A5142			P91 TO AB0340A DISCONNECT BRACKET											
0011	24		PK		23-3	33-29-11	D11416	11			D40054P	4			YC051-YN260
0012	24		PK		23-3	33-22-11	D11416	12			D40054P	2			YC051-YN260
0021	22		PA		23-3	38-41-11	D11416	21			D40054P	3			ALL
0025	24		PK		23-3	33-29-11	D11416	25			D40054P	7			ALL
0026	22		PA		23-3	33-26-11	D11416	26			D40054P	1			ALL
0040	18		PA		24-5	33-35-11	D11416	40			D40102P	6			ALL
0051	18		PA		24-5	33-22-11	D40102P	13			D11416	35			ALL
0052	18		PA		24-5	33-22-11	D40102P	14			D11416	36			ALL
0053	22		PA		23-3	33-22-11	D40054P	10			D11416	13			YC051-YN260
0054	20		PA		23-5	SPARE	D40054P	5			D11416	CAP	Y		ALL
0055	20		PA		23-5	SPARE	D40054P	6			D11416	CAP	Y		ALL
0056	20		PA		23-5	SPARE	D40054P	8			D11416	CAP	Y		ALL
0059	22		PA		1-4	33-22-11	D11416	14			SM00012		S		YN501-YR328
0089	18		PA		24-5	33-22-11	D40102P	26			D11416	1			YN501-YR328
0090	22		PA		1-4	33-22-11	D11416	3			SM00012		S		YN501-YR328
0091	18		PA		24-5	33-22-11	D40102P	27			D11416	2	18		YN501
0091	18		PA		24-5	33-22-11	D11416	2	18		D40102P	27			YR301-YR328
0092	22		PA		23-2	33-22-11	D40054P	2			SM00012		S		YN501-YR328
0093	22		PA		21-10	33-22-11	D11416	13			SP00897		S		YN501-YR328
0094	22		PA		21-10	33-22-11	D11416	12			SP00899		S		YN501-YR328
2428B	18		PB	PC	25-6	33-23-11	D40102P	17			GD00590	AC..	E		ALL
2428R	18		PB	PC	0-0	33-23-11	D11416	28			D40102P	7			YC051-YN501
2428R	18		PB	PC	0-0	33-23-11	D40102P	7			D11416	28			YR301-YR328
2429B	18		PB	PD	25-6	33-23-11	D40102P	18			GD00590	AC..	E		ALL
2429R	18		PB	PD	0-0	33-23-11	D11416	29			D40102P	8			YC051-YN501
2429R	18		PB	PD	0-0	33-23-11	D40102P	8			D11416	29			YR301-YR328
2430B	18		PB	PE	25-6	33-23-11	D40102P	19			GD00590	AC..	E		ALL
2430R	18		PB	PE	0-0	33-23-11	D11416	30			D40102P	9			YC051-YN501
2430R	18		PB	PE	0-0	33-23-11	D40102P	9			D11416	30			YR301-YR328
2431B	18		PB	PF	25-6	33-23-11	D40102P	20			GD00592	AC..	E		ALL
2431R	18		PB	PF	0-0	33-23-11	D11416	31			D40102P	10			YC051-YN501
2431R	18		PB	PF	0-0	33-23-11	D40102P	10			D11416	31			YR301-YR328
2432B	18		PB	PG	25-6	33-23-12	D40102P	21			GD00592	AC..	E		ALL
2432R	18		PB	PG	0-0	33-23-12	D11416	32			D40102P	11			YC051-YN501
2432R	18		PB	PG	0-0	33-23-12	D40102P	11			D11416	32			YR301-YR328
2433B	18		PB	PH	25-6	33-23-12	D40102P	22			GD00592	AC..	E		ALL
2433R	18		PB	PH	0-0	33-23-12	D11416	33			D40102P	1			YC051-YN501
2433R	18		PB	PH	0-0	33-23-12	D40102P	1			D11416	33			YR301-YR328
2434B	18		PB	PI	25-6	33-23-12	D40102P	23			GD00594	AC..	E		ALL

WIRE LIST

D280A108

91-21-11

Section W5140

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From			To					
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5142		286A5142			P91 TO AB0340A DISCONNECT BRACKET (continued)											
2434R		18		PB	PI	0-0	33-23-12	D11416				D40102P	2			YC051-YN501
2434R		18		PB	PI	0-0	33-23-12	D40102P				D11416	34			YR301-YR328
2435B		18		PB	PJ	25-6	33-23-12	D40102P				GD00594	AC..	E		YC051-YL999, YR301-YR328
2435R		18		PB	PJ	0-0	33-23-12	D11416				D40102P	15			YC051-YL999
2435R		18		PB	PJ	0-0	33-23-12	D40102P				D11416	15			YR301-YR328
2436B		18		PB	PK	25-6	33-23-12	D40102P				GD00594	AC..	E		YC051-YL999, YR301-YR328
2436R		18		PB	PK	0-0	33-23-12	D11416				D40102P	5			YC051-YL999
2436R		18		PB	PK	0-0	33-23-12	D40102P				D11416	27			YR301-YR328
5516		22		PA		24-5	21-42-11	D11416				D40102P	29			ALL
5517		22		PA		24-5	21-42-11	D11416				D40102P	30			ALL
W5146		286A5146			SEC 46 TO WTR QTY AND MISC											
0001		22		PA		29-2	38-41-11	D00192				D40148J	1			ALL
0002		22		PA		29-2	38-41-11	D00192				D40148J	2			ALL
0003		22		PA		29-2	38-41-11	D00192				D40148J	3			ALL
0004		20		PA		4-7	38-41-11	D00192				GD00070	DC..	1		ALL
0005		20		PA		4-7	38-41-11	D00192				GD00070	ST..	1		ALL
0101		18		PA		12-7	38-32-12	D11702			18	D40152P	1			ALL
0105		20		PA		1-3	38-32-13	D11702				SM00020		S		YC051-YC052
0105		20		PA		4-1	38-32-13	D11702				SM00020		S		YC053-YL999, YR301-YR328
0105		20		PA		11-2	38-32-13	D11702				SM00020		S		YN231-YN501
0107		18		PA		5-5	38-32-12	D11702			18	GD11894	DC..	1		YC051-YL999, YR301-YR328
0107		18		PA		6-0	38-32-12	D11702			18	GD11894	DC..	1		YN231-YN501
0110		18		PA		5-5	38-32-12	D11702			18	GD11894	ST..	1		YC051-YL999, YR301-YR328
0110		18		PA		6-0	38-32-12	D11702			18	GD11894	ST..	1		YN231-YN501
0113		20		PA		5-5	38-32-12	D11702				GD11894	DC..	1		YC051-YL999, YR301-YR328
0113		20		PA		6-0	38-32-12	D11702				GD11894	DC..	1		YN231-YN501
0115		20		PA		5-5	38-32-12	D11702				GD11894	DC..	1		YC051-YL999, YR301-YR328
0115		20		PA		6-0	38-32-12	D11702				GD11894	DC..	1		YN231-YN501
0122		18		PA		20-0	38-32-12	D40150J				D11702	2	18		YC051-YL999, YR301-YR328
0122		18		PA		20-1	38-32-12	D40150J				D11702	2	18		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W5140

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type
W5146	286A5146				SEC 46 TO WTR QTY AND MISC (continued)										
0126	20		PA		40-7	38-32-12	D11786		2		D11716		1		YC051-YC052
0126	20		PA		40-11	38-32-12	D11786		2		D11716		1		YC053-YL999, YR301-YR328
0126	20		PA		40-9	38-32-12	D11786		2		D11716		1		YN231-YN501
0127	20		PA		38-2	38-32-12	D11786		3		D40152P		2		YC051-YC052
0127	20		PA		38-5	38-32-12	D11786		3		D40152P		2		YC053-YL999, YR301-YR328
0127	20		PA		38-3	38-32-12	D11786		3		D40152P		2		YN231-YN501
0132	20		PA		15-0	38-32-12	D40150J		12		D11716		2		ALL
0203	20		PA		15-0	38-32-13	D11702		3		L01309	CAP	Y		YC051-YL999, YR301-YR328
0203	20		PA		15-1	38-32-13	D11702		3		L01309	CAP	Y		YN231-YN501
0211	22		PA		15-1	38-32-13	D11788		1		SM00002		S		YC051-YC052
0211	22		PA		12-3	38-32-13	D11788		1		SM00002		S		YC053-YL999, YR301-YR328
0211	22		PA		6-11	38-32-13	D11788		1		SM00002		S		YN231-YN501
0212	20		PA		15-5	38-32-13	D11788		2		GD11894	DC..	1		ALL
0213	20		PA		15-5	38-32-13	D11788		3		GD11894	ST..	1		ALL
0218	22		PA		1-3	38-32-13	D11702		18		SM00002		S		YC051-YC052
0218	22		PA		4-1	38-32-13	D11702		18		SM00002		S		YC053-YL999, YR301-YR328
0218	22		PA		11-2	38-32-13	D11702		18		SM00002		S		YN231-YN501
0224	20		PA		20-8	38-32-13	D40148J		4		D11702		4		YC051-YL999, YR301-YR328
0224	20		PA		20-9	38-32-13	D40148J		4		D11702		4		YN231-YN501
0225	22		PA		20-0	38-32-13	D40148J		5		SM00002		S		YC051-YC052
0225	22		PA		17-2	38-32-13	D40148J		5		SM00002		S		YC053-YL999, YR301-YR328
0225	22		PA		10-7	38-32-13	D40148J		5		SM00002		S		YN231-YN501
0227	20		PA		20-4	38-32-13	D40148J		7		GD11894	DC..	1		ALL
0228	20		PA		20-8	38-32-13	D40148J		8		D11702		8		YC051-YL999, YR301-YR328
0228	20		PA		20-9	38-32-13	D40148J		8		D11702		8		YN231-YN501
0229	22		PA		20-8	38-32-13	D40148J		9		D11702		9		YC051-YL999, YR301-YR328
0229	22		PA		20-9	38-32-13	D40148J		9		D11702		9		YN231-YN501
0230	20		PA		20-0	38-32-13	SM00020			S	D40148J		10		YC051-YC052
0230	20		PA		17-2	38-32-13	SM00020			S	D40148J		10		YC053-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W5140

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5146	286A5146				SEC 46 TO WTR QTY AND MISC (continued)										
0230	20		PA		10-7	38-32-13	SM00020				D40148J	10			YN231-YN501
0250	20		PA		14-4	38-32-13	SM00020				L01309	CAP	Y		YC051-YC052
0250	20		PA		11-6	38-32-13	SM00020				L01309	CAP	Y		YC053-YL999, YR301-YR328
0250	20		PA		6-2	38-32-13	SM00020				L01309	CAP	Y		YN231-YN501

WIRE LIST
D280A108

91-21-11
Section W5140
Page 4 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5156	286A5156			PSEU & AIR/GND SYS: M2061 & J22,J20 TO E/E BAY (ROUTE LEFT)											
0001	18		PA		24-11	52-71-12	D40498P	1	18		S00197		C	C	YC051-YC055
0001	18		PA		24-6	52-71-12	D40498P	1	18		S00197		C	C	YC056-YD158
0001	18		PA		24-10	52-71-12	D40498P	1	18		S00197		C	C	YL951-YR328
0002	18		PA		3-0	52-71-12	S00197	NO	C		GD01322	DC..	E		YC051-YC055, YL951-YN501
0002	18		PA		3-1	52-71-12	S00197	NO	C		GD01322	DC..	E		YC056-YD158, YR301-YR328
0003	20		CQ		8-3	52-71-13	D40576P	10			D40666P	26			YC051-YD158, YL951-YL999, YR301-YR328
0003	20		PA		8-3	52-71-13	D40576P	10			D40666P	26			YN231-YN501
0004	20		PA		14-11	52-71-13	D40676P	3			D46116P	8			YC051-YD158, YL951-YR328
0005	20		CQ		6-4	52-71-13	D40676P	4			D48112P	A06			YC051-YD158, YL951-YR328
0006	20		PA		6-4	52-71-13	D40676P	5			D48112P	A07			YC051-YD158, YL951-YR328
0007	20		PA		6-4	52-71-13	D40676P	6			D48112P	A05			YC051-YD158, YL951-YR328
0008	20		PA		13-1	52-71-13	D10982	5			D46116P	9			YC051-YD158, YL951-YR328
0010	22		PA		22-11	31-35-03	D40670P	5			D40462P	A06			YN236-YR328
0011	24		PK		8-7	34-49-11	D40576P	9			D40680P	9			YC053-YD158, YL951-YL999, YR301-YR328
0011	24		PK		8-7	34-49-11	D40680P	9			D40576P	9			YN231-YN501
0012	24		PK		11-10	34-49-11	D40680P	13			D40454P	A07			YC053-YD158, YL951-YR328
0013	24		PK		11-10	34-49-11	D40680P	14			D40454P	B06			YC053-YD158, YL951-YR328
0014	24		PK		11-10	34-49-11	D40680P	15			D40454P	B07			YC053-YD158, YL951-YR328
0016	22		PA		15-4	34-41-11	D40578P	17			D40670P	22			YC053-YD157, YN231-YN501
0016	22		PA		15-4	34-41-11	D40670P	22			D40578P	17			YD158, YL951-YL999, YR301-YR328
0021	20		PA		13-1	SPARE	D10982	21			D46116P	14			YC051-YD157
0021	20		PA		2-4	33-45-11	D10982	21			SM00004		S		YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5150

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To					
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W5156	286A5156				PSEU & AIR/GND SYS: M2061 & J22,J20 TO E/E BAY (ROUTE LEFT) (continued)											
0022	24		PK		11-8	34-49-11	D40680P		22			D40458P	A03			YC053-YD158, YL951-YR328
0023	24		PK		11-8	34-49-11	D40680P		23			D40458P	A04			YC053-YD158, YL951-YR328
0024	22		PA		8-3	23-71-01	D40576P		25			D40666P	31			YC051-YD158, YL951-YR328
0025	18		PA		8-3	23-71-01	D40576P		24			D40666P	29	18		YC051-YD158, YL951-YR328
0026	24		PK		11-8	34-41-11	D40680P		24			D40458P	A05			YC053-YD158, YL951-YR328
0027	22		PA		15-0	34-41-11	D40680P		25			D46116P	31			YC053-YC065
0027	22		PA		15-1	34-41-11	D40680P		25			D46116P	31			YC067-YD158, YL951-YR328
0028	22		PA		23-0	34-41-11	D40460P		B07			D40670P	21			YC053-YC055
0028	22		PA		22-9	34-41-11	D40460P		B07			D40670P	21			YC056-YD158, YL951-YR328
0049	20		PA		11-4	33-45-11	D46116P		14			SM00004		S		YL951-YR328
0054	24		GK		16-1	21-31-22	D40456P		A04			D40878P	1			YC053
0054	24		PK		24-0	21-31-22	D40456P		A04			D40878P	1			YC055, YC060-YC064
0054	24		PK		16-1	21-31-22	D40456P		A04			D40878P	1			YC067-YD158, YL951-YR328
0055	24		GK		16-1	21-31-22	D40456P		B04			D40878P	2			YC053
0055	24		PK		24-0	21-31-22	D40456P		B04			D40878P	2			YC055, YC060-YC064
0055	24		PK		16-1	21-31-22	D40456P		B04			D40878P	2			YC067-YD158, YL951-YR328
0056	20		CQ		16-1	21-31-22	D40456P		A10			D40878P	3			YC053, YC067-YD158, YL951-YR328
0056	20		CQ		24-0	21-31-22	D40456P		A10			D40878P	3			YC055, YC060-YC064
0057	22		PA		12-0	26-16-21	D40456P		A05			D40640P	12			YC053
0057	22		PA		24-0	26-16-21	D40456P		A05			D40640P	12			YC055, YC060-YC064
0057	22		PA		11-1	26-16-21	D40462P		A05			D40456P	A05			YC067-YD158, YL951-YR328
0402	22		PA		16-6	21-33-11	D40578P		19			SP00575		W		YC060-YC064
0402	22		PA		23-8	21-33-11	D40578P		19			D46116P	CAP	Y		YL951-YL952, YN231-YN232
0402	22		PA		23-8	21-33-11	D40578P		19			D46116P	11			YL953-YL999, YN233-YR328
0403	22		CQ		11-6	31-53-11	D10982		53			SP00573		W		YC060-YC064

WIRE LIST

D280A108

91-21-11

Section W5150

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5156	286A5156			PSEU & AIR/GND SYS: M2061 & J22,J20 TO E/E BAY (ROUTE LEFT) (continued)											
0499	22		CQ		16-6	31-53-11	D40578P	39			SM00005		W		YC060-YC064
0499	22		CQ		23-8	31-53-11	D40578P	39			D46116P	CAP	Y		YL951-YL952, YN231-YN232
0499	22		CQ		23-8	31-53-11	D40578P	39			D46116P	41			YL953-YL999, YN233-YR328
0501	20		CQ		21-2	22-11-12	D11142	46			D40452P	A01			YC051-YD158, YL951-YR328
0502	20		CQ		21-2	22-11-12	D11142	47			D40452P	A02			YC051-YD158, YL951-YR328
0503	22		CQ		17-9	23-22-11	D40670P	1			D40456P	A01			YC051-YC055
0503	22		CQ		17-5	23-22-11	D40670P	1			D40456P	A01			YC056-YD158, YL951-YR328
0504	22		CQ		17-9	23-22-11	D40670P	2			D40456P	A02			YC051-YC055
0504	22		CQ		17-5	23-22-11	D40670P	2			D40456P	A02			YC056-YD158, YL951-YR328
0505	22		CQ		17-9	23-22-11	D40670P	3			D40456P	A03			YC051-YC055
0505	22		CQ		17-5	23-22-11	D40670P	3			D40456P	A03			YC056-YD158, YL951-YR328
0506	22		PA		32-8	27-32-11	D11138	28			D40462P	A01			YC051-YC055
0506	22		PA		32-4	27-32-11	D11138	28			D40462P	A01			YC056-YD158, YL951-YR328
0508	22		PA		32-8	27-32-11	D11138	48			D40462P	A03			YC051-YC055
0508	22		PA		32-4	27-32-11	D11138	48			D40462P	A03			YC056-YD158, YL951-YR328
0509	22		PA		21-7	34-31-11	D11142	5			D40498P	2			YC051-YC055
0509	22		PA		21-8	34-31-11	D11142	5			D40498P	2			YC056-YD158, YL951-YR328
0510	22		PA		32-8	34-33-11	D11142	55			D40460P	A01			YC051-YC055
0510	22		PA		32-4	34-33-11	D11142	55			D40460P	A01			YC056-YD158, YL951-YR328
0511	22		PA		21-2	34-49-11	D11142	29			D40454P	A01			YC051-YD158, YL951-YR328
0512	22		PA		21-1	34-45-11	D11138	47			D40454P	A02			YC051-YD158, YL951-YR328
0513	22		PA		21-2	34-51-11	D11142	15			D40452P	B08			YC051-YD158, YL951-YR328
0514	22		PA		14-7	34-53-11	D48114P	A05			D11142	26			YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5150

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5156	286A5156				PSEU & AIR/GND SYS: M2061 & J22,J20 TO E/E BAY (ROUTE LEFT) (continued)										
0515	22		PA		14-7	34-55-11	D11142		32		D48114P		B05		YC051-YD158, YL951-YR328
0516	22		PA		32-8	34-57-11	D11142		16		D40460P		A02		YC051-YC055
0516	22		PA		32-4	34-57-11	D11142		16		D40460P		A02		YC056-YD158, YL951-YR328
0517	22		PA		21-0	34-21-11	D11138		53		D40452P		A04		YC051-YD158, YL951-YR328
0518	20		PA		27-3	23-71-01	D11138		51		D40456P		A07		YC051-YC055
0518	20		PA		26-11	23-71-01	D11138		51		D40456P		A07		YC056-YD158, YL951-YR328
0519	20		PA		27-3	23-71-01	D11138		30		D40456P		A08		YC051-YC055
0519	20		PA		26-11	23-71-01	D11138		30		D40456P		A08		YC056-YD158, YL951-YR328
0520	22		PA		21-6	23-12-11	D11138		16		D40498P		11		YC051-YD158, YL951-YR328
0521	22		PA		21-2	34-61-17	D11142		25		D40454P		A03		YC051-YD158, YL951-YR328
0522	22		PA		23-2	31-31-15	D40670P		4		D40462P		A04		YC051-YC055
0522	22		PA		22-11	31-31-15	D40670P		4		D40462P		A04		YC056-YD158, YL951-YR328
0528	22		PA		8-3	31-31-11	D40576P		1		D40666P		1		YC051-YD158, YL951-YR328
0529	22		PA		6-2	31-31-11	D48112P		B02		D40666P		2		YC051-YD158, YL951-YR328
0533	22		PA		32-10	31-31-15	D11142		45		D40462P		A09		YC051-YC055
0533	22		PA		32-6	31-31-15	D11142		45		D40462P		A09		YC056-YD158, YL951-YR328
0534	22		PA		33-0	31-31-15	D10982		7		D40462P		A10		YC051-YC055
0534	22		PA		32-9	31-31-15	D10982		7		D40462P		A10		YC056-YD158, YL951-YR328
0535	22		PA		33-0	31-31-15	D10982		18		D40462P		A11		YC051-YC055
0535	22		PA		32-9	31-31-15	D10982		18		D40462P		A11		YC056-YD158, YL951-YR328
0536	22		PA		33-0	31-31-15	D10982		35		D40462P		A12		YC051-YC055
0536	22		PA		32-9	31-31-15	D10982		35		D40462P		A12		YC056-YD158, YL951-YR328
0537	22		PA		33-0	31-31-15	D10982		44		D40462P		A13		YC051-YC055
0537	22		PA		32-9	31-31-15	D10982		44		D40462P		A13		YC056-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5150

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5156	286A5156			PSEU & AIR/GND SYS: M2061 & J22,J20 TO E/E BAY (ROUTE LEFT) (continued)											
0538	22		PA		33-0	31-31-15	D10982				D40462P	A14			YC051-YC055
0538	22		PA		32-9	31-31-15	D10982				D40462P	A14			YC056-YD158, YL951-YR328
0539	22		PA		33-0	31-31-15	D10982				D40462P	A15			YC051-YC055
0539	22		PA		32-9	31-31-15	D10982				D40462P	A15			YC056-YD158, YL951-YR328
0540	22		CQ		27-5	49-41-11	D11142	31	VP		D40456P	A06			YC051-YC055
0540	22		CQ		27-1	49-41-11	D11142	31	VP		D40456P	A06			YC056-YD158, YL951-YR328
0541	22		PA		14-5	24-33-11	D11138				D48112P	A02			YC051-YD158, YL951-YR328
0542	22		PA		21-2	27-53-11	D11142				D40452P	A05			YC051-YD158, YL951-YR328
0544	22		CQ		21-0	32-64-11	D40452P		A06		D11138	61			YC051-YD158, YL951-YR328
0545	20		CQ		3-6	32-64-11	D11138		41		GD00044	DC..	1		YC051-YD158, YL951-YR328
0546	22		PA		25-2	32-64-11	D10982		6		D40578P	1			YC051-YD158, YL951-YR328
0547	22		PA		25-2	32-64-11	D10982		1		D40578P	2			YC051-YD158, YL951-YR328
0548	22		CQ		12-9	29-23-11	D46116P		27		D11138	7			YC051-YD158, YL951-YR328
0549	22		PA		25-2	29-23-11	D40578P		3		D10982	39			YC051-YD158, YL951-YR328
0550	22		CQ		32-9	29-23-11	D40462P		B17		D11138	2			YC051-YD158, YL951-YR328
0551	22		PA		25-2	32-64-11	D10982		36		D40578P	4			YC051-YD158, YL951-YR328
0552	22		PA		25-2	32-64-11	D10982		26		D40578P	5			YC051-YD158, YL951-YR328
0553	22		PA		25-2	32-64-11	D10982		34		D40578P	6			YC051-YD158, YL951-YR328
0554	22		PA		25-2	32-64-11	D10982		8		D40578P	7			YC051-YD158, YL951-YR328
0555	22		PA		25-2	32-64-11	D10982		25		D40578P	8			YC051-YD158, YL951-YR328
0556	22		PA		25-2	32-64-11	D10982		59		D40578P	9			YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5150

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5156	286A5156				PSEU & AIR/GND SYS: M2061 & J22,J20 TO E/E BAY (ROUTE LEFT) (continued)										
0560	22		PA		21-7	32-42-11	D40498P		4		D11142		48		YC051-YC055
0560	22		PA		21-8	32-42-11	D40498P		4		D11142		48		YC056-YD158, YL951-YR328
0561	22		PA		21-7	32-42-11	D40498P		5		D11142		49		YC051-YC055
0561	22		PA		21-8	32-42-11	D40498P		5		D11142		49		YC056-YD158, YL951-YR328
0562	22		CQ		14-9	27-62-11	D40670P		29		D46116P		24		YC051-YC065
0562	22		CQ		14-10	27-62-11	D40670P		29		D46116P		24		YC067-YD158, YL951-YR328
0565	22		CQ		12-7	27-62-11	D40452P		A10		D40636P		8		YC051-YD158, YL951-YR328
0566	22		CQ		12-7	27-62-11	D40452P		B10		D40636P		9		YC051-YD158, YL951-YR328
0567	22		PA		33-0	27-32-11	D10982		24		D40462P		A16		YC051-YC055
0567	22		PA		32-9	27-32-11	D10982		24		D40462P		A16		YC056-YD158, YL951-YR328
0568	22		CQ		8-3	23-22-11	D40576P		6		D40666P		6		YC051-YD158, YL951-YR328
0569	20		PA		6-4	52-71-13	D40676P		7		D48112P		A08		YC051-YD158, YL951-YL999, YR301-YR328
0570	22		PA		14-10	32-64-21	D10982		40		D48114P		A04		YC051-YD158, YL951-YR328
0572	22		PA		14-10	32-64-21	D10982		41		D48114P		B04		YC051-YD158, YL951-YR328
0573	22		PA		21-4	32-64-21	D10982		17		D40452P		B01		YC051-YD158, YL951-YR328
0574	22		PA		13-1	32-64-21	D10982		14		D46116P		3		YC051-YD158, YL951-YR328
0575	22		PA		12-9	32-64-21	D11138		23		D46116P		4		YC051-YD158, YL951-YR328
0576	22		PA		13-1	31-53-11	D46116P		5		D10982		53		YC051-YC059, YC065-YD158, YL951-YL952, YN231-YN232
0576	22		CQ		13-1	31-53-11	D46116P		5		D10982		53		YL953-YL999, YN233-YR328
0577	22		PA		13-1	31-53-11	D46116P		6		D10982		29		YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5150

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W5156	286A5156				PSEU & AIR/GND SYS: M2061 & J22,J20 TO E/E BAY (ROUTE LEFT) (continued)												
0578	22		PA		13-1	31-53-11		D46116P		1		D10982		42		YC051-YD158, YL951-YR328	
0579	22		PA		13-1	31-53-11		D10982		52		D46116P		17		YC051-YD158, YL951-YR328	
0581	22		PA		21-2	31-53-11		D11142		7		D40454P		A08		YC051-YD158, YL951-YR328	
0582	22		CQ		33-0	31-53-11		D10982		15		D40462P		A18		YC051-YC055	
0582	22		CQ		32-9	31-53-11		D10982		15		D40462P		A18		YC056-YD158, YL951-YR328	
0583	22		PA		33-0	31-53-11		D10982		51		D40462P		A19		YC051-YC055	
0583	22		PA		32-9	31-53-11		D10982		51		D40462P		A19		YC056-YD158, YL951-YR328	
0584	22		CQ		14-11	29-25-11		D46116P		13		D40676P		1		YC051-YD158, YL951-YR328	
0585	18		CQ		17-11	29-25-11		D40676P		2		D40456P		F		YC051-YD158, YL951-YR328	
0586	24		PK		7-2	31-62-14		D40724P		A01		D40460P		B04		YC051-YC055	
0586	24		PK		7-3	31-62-14		D40724P		A01		D40460P		B04		YC056-YD158, YL951-YR328	
0587	24		PK		7-2	31-62-14		D40460P		A09		D40724P		A07		YC051-YC055	
0587	24		PK		7-3	31-62-14		D40460P		A09		D40724P		A07		YC056-YD158, YL951-YR328	
0588	24		B6		6-2	34-41-11		D40666P		25		D48114P		A03		YC051-YC052	
0588	24		B6		6-2	SPARE		D40666P		25		D48114P		A03		YD158, YL951-YR328	
0594	24		PK		6-2	34-41-11		D40666P		30		D48112P		A04		YC051-YC052	
0594	24		PK		6-2	SPARE		D40666P		30		D48112P		A04		YD158, YL951-YR328	
0595	20		CQ		21-4	22-11-12		D10982		10		D40452P		A03		YC051-YD158, YL951-YR328	
0598	22		PA		21-4	32-64-21		D10982		43		D40452P		B09		YC051-YD158, YL951-YR328	
0600	22		PA		32-6	32-64-21		D10982		31		D40594P		B04		YC051-YC055	
0600	22		PA		32-2	32-64-21		D10982		31		D40594P		B04		YC056-YD158, YL951-YR328	
0601	18		PA		6-1	32-31-11		TB0040K		E002	1	GD00412		AC.. E	*	YC051-YD158, YL951-YR328	
0602	22		PA		1-11	32-31-11		D11138		39		SM00002		S		YC051-YD158, YL951-YR328	
0603	22		PA		1-11	32-31-11		D11138		36		SM00002		S		YC051-YD158, YL951-YR328	

WIRE LIST

D280A108

91-21-11

Section W5150

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5156	286A5156				PSEU & AIR/GND SYS: M2061 & J22,J20 TO E/E BAY (ROUTE LEFT) (continued)										
0604	22		PA		14-7	32-31-11	SM00002		S		D40670P	31			YC051-YD158, YL951-YR328
0605	22		CQ		16-0	32-31-11	D11138		20		D40670P	9			YC051-YD158, YL951-YR328
0606	22		CQ		16-0	32-31-11	D11138		21		D40670P	10			YC051-YD158, YL951-YR328
0607	22		CQ		16-0	32-31-11	D11138		35		D40670P	11			YC051-YD158, YL951-YR328
0608	22		CQ		16-0	32-31-11	D11138		58		D40670P	12			YC051-YD158, YL951-YR328
0609	22		CQ		16-0	32-31-11	D11138		59		D40670P	13			YC051-YD158, YL951-YR328
0610	22		PA		32-3	23-27-12	D11142		12		D40594P	A07			YC051-YC055
0610	22		PA		32-0	23-27-12	D11142		12		D40594P	A07			YC056-YD157
0610	22		PA		32-0	23-27-38	D11142		12		D40594P	A07			YD158, YL951-YR328
0612	22		PA		3-8	32-31-11	D11142		57		GD00044	DC..	1		YC051-YD158, YL951-YR328
0614	22		CQ		11-6	32-31-11	D40452P		B04		D40670P	14			YC051-YD158, YL951-YR328
0615	22		PA		21-2	34-21-16	D11142		50		D40452P	A08			YC051-YD158, YL951-YR328
0616	22		PA		19-2	23-32-12	D40578P		14		D40498P	3			YC051-YD157
0616	22		PA		21-6	23-32-14	D11138		3		D40498P	3			YD158, YL951-YN260
0616	22		PA		21-6	44-21-22	D11138		3		D40498P	3			YN501-YR328
0617	22		PA		19-2	23-32-12	D40578P		15		D40498P	6			YC051-YD157
0618	22		CQ		12-0	23-32-12	D40670P		5		D40498P	7			YC051-YD157
0618	22		PA		21-6	23-32-14	D11138		13		D40498P	7			YD158, YL951-YN260
0618	22		PA		21-6	44-21-22	D11138		13		D40498P	7			YN501
0618	22		CQ		21-6	44-21-22	D11138		13		D40498P	7			YR301-YR328
0619	22		PA		22-4	SPARE	D40670P		6		D40594P	A10			YC067-YD157
0622	14		CQ		25-0	21-25-11	D40678P		1		D41824P	1			YC051-YC055
0622	14		CQ		24-9	21-25-11	D40678P		1		D41824P	1			YC056-YD158, YL951-YL999, YR301-YR328
0623	14		CQ		25-0	21-25-11	D40678P		2		D41824P	2			YC051-YC055
0623	14		CQ		24-9	21-25-11	D40678P		2		D41824P	2			YC056-YD158, YL951-YL999, YR301-YR328
0624	14		CQ		25-0	21-25-11	D40678P		3		D41824P	3			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5150

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY	Description Fam FT-IN Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W5156	286A5156	PSEU & AIR/GND SYS: M2061 & J22,J20 TO E/E BAY (ROUTE LEFT) (continued)									
0624	14	CQ	24-9	21-25-11	D40678P	3	D41824P	3			YC056-YD158, YL951-YL999, YR301-YR328
0625	14	CQ	8-3	21-25-11	D40678P	4	D40576P	22			YC051-YD158, YL951-YL999, YR301-YR328
0626	14	CQ	8-3	21-25-11	D40678P	5	D40576P	18			YC051-YD158, YL951-YL999, YR301-YR328
0627	14	CQ	8-3	21-25-11	D40678P	6	D40576P	20			YC051-YD158, YL951-YL999, YR301-YR328
0628	22	PA	8-3	21-25-11	D40666P	8	D40576P	15			YC051-YD158, YL951-YL999, YR301-YR328
0629	22	PA	14-11	21-25-11	D40676P	12	D46116P	15			YC051-YD158, YL951-YL999, YR301-YR328
0630	20	PA	12-9	52-71-13	D11138	9	D46116P	10			YC051-YD158, YL951-YL999, YR301-YR328
0631	22	PA	12-0	32-41-11	D40670P	15	D40498P	18			YC051-YD158, YL951-YR328
0632	22	PA	12-0	32-41-11	D40670P	16	D40498P	8			YC051-YD158, YL951-YR328
0633	22	PA	15-4	32-41-11	D40670P	17	D40578P	10			YC051-YD158, YL951-YR328
0634	22	PA	12-0	32-41-11	D40670P	18	D40498P	9			YC051-YD158, YL951-YR328
0635	22	PA	12-0	32-41-11	D40670P	19	D40498P	10			YC051-YD158, YL951-YR328
0636	18	CQ	9-5	38-31-31	D40576P	14	D40636P	5			YL951-YR328
0637	18	CQ	3-3	38-31-31	D12092	1	GD06106	DC..	E		YL951-YR328
0638	18	CQ	25-8	38-31-31	D12092	2	D40636P	7			YL951-YL999, YR301-YR328
0638	18	CQ	25-7	38-31-31	D12092	2	D40636P	7			YN231-YN501
0639	18	CQ	25-8	38-31-31	D12092	3	D40636P	6			YL951-YL999, YR301-YR328
0639	18	CQ	25-7	38-31-31	D12092	3	D40636P	6			YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W5150

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5156	286A5156				PSEU & AIR/GND SYS: M2061 & J22,J20 TO E/E BAY (ROUTE LEFT) (continued)											
0640	22		CQ		14-7	21-27-31		D40636P		1		D46116P		16		YC051-YD158, YL951-YR328
0641	22		CQ		14-7	21-27-31		D40636P		2		D46116P		28		YC051-YD158, YL951-YR328
0642	22		CQ		14-7	21-27-31		D40636P		3		D46116P		29		YC051-YD158, YL951-YR328
0644	22		PA		8-3	23-15-15		D40576P		21		D40666P		27		YC051-YD157
0645	20		PA		12-0	23-11-16		D40498P		29		D40670P		28		YD158
0645	20		PA		12-0	SPARE		D40498P		29		D40670P		28		YL951-YL999, YR301-YR328
0646	20		PA		22-9	SPARE		D40460P		A08		D40670P		28		YC067-YD157, YN231-YN501
0648	22		PA		23-5	SPARE		D40642P		12		D40594P		B10		YC067-YD157
0650	18		HA		4-10	32-64-11		TB0042K		E001	1	GD00030		AC..	E	YC051-YD158, YL951-YR328
0651	18		HA		6-1	32-64-11		TB0040K		E001	1	GD00412		AC..	E	* YC051-YD158, YL951-YR328
0653	20		PA		3-6	23-32-14		D11138		11		GD00044		DC..	1	YD158, YL951-YN260
0653	20		PA		3-6	44-21-22		D11138		11		GD00044		DC..	1	YN501-YR328
0654	22		PA		21-10	23-32-14		D10982		21		D40498P		6		YD158
0654	22		PA		20-1	23-32-14		SM00004			S	D40498P		6		YL951-YN260
0654	22		PA		20-1	44-21-22		SM00004			S	D40498P		6		YN501-YR328
0656	22		PA		21-0	32-31-11		D11138		19		D40452P		B03		YC051-YD158, YL951-YR328
0657	22		PA		25-2	32-44-11		D40578P		11		D10982		61		YC051-YD158, YL951-YR328
0659	22		PA		20-3	23-32-14		D46116P		7		D40498P		25		YD158, YL951-YN260
0659	22		PA		20-3	44-21-22		D46116P		7		D40498P		25		YN501-YR328
0660	20		CQ		22-7	SPARE		D40666P		9		D40594P		A08		YC051-YC055
0660	20		CQ		22-3	SPARE		D40666P		9		D40594P		A08		YC056-YD158, YL951-YR328
0667	24		PK		8-3	SPARE		D40666P		21		D40576P		8		YC051-YD158, YL951-YR328
0668	22		PA		22-11	SPARE		D40666P		20		D40460P		B01		YC051-YC055
0668	22		PA		22-8	SPARE		D40666P		20		D40460P		B01		YC056-YC065, YD158, YL951-YR328
0669	22		PA		12-8	34-61-18		D40642P		1		D40454P		B10		YC051-YC058
0669	22		PA		12-8	31-32-15		D40642P		1		D40454P		B10		YC059-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5150

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5156	286A5156			PSEU & AIR/GND SYS: M2061 & J22,J20 TO E/E BAY (ROUTE LEFT) (continued)											
0670	20		PA		22-8	49-62-11	D40642P		11		D40724P	A17			YC051-YD158, YL951-YR328
0671	22		PA		22-4	SPARE	D48114P		B07		D40594P	A02			YC051-YC055
0671	22		PA		22-1	SPARE	D48114P		B07		D40594P	A02			YC056-YD158, YL951-YR328
0672	22		PA		22-4	SPARE	D48114P		B08		D40594P	B02			YC051-YC055
0672	22		PA		22-1	SPARE	D48114P		B08		D40594P	B02			YC056-YD158, YL951-YR328
0673	22		PA		22-4	SPARE	D48114P		B09		D40594P	B01			YC051-YC055
0673	22		PA		22-1	SPARE	D48114P		B09		D40594P	B01			YC056-YD158, YL951-YR328
0674	22		PA		22-4	SPARE	D48114P		B10		D40594P	A01			YC051-YC055
0674	22		PA		22-1	SPARE	D48114P		B10		D40594P	A01			YC056-YD158, YL951-YR328
0695	22		CQ		13-1	31-53-11	D40458P		B02		SM00005		W		YC060-YC064
0695	22		CQ		19-9	31-53-11	D46116P		40		D40458P	B02			YL953-YL999, YN233-YR328
0696	22		CQ		20-0	31-53-11	D40458P		B03		SP00795		W		YC060-YC064
0696	22		CQ		19-9	31-53-11	D46116P		39		D40458P	B03			YL953-YL999, YN233-YR328
0697	22		CQ		26-8	31-53-11	D40458P		B04		TB0501Y	A025	1A		YC060-YC064
0697	22		CQ		19-9	31-53-11	D46116P		37		D40458P	B04			YL953-YL999, YN233-YR328
0698	22		CQ		16-6	31-53-11	SP00573			W	TB0501Y	B025	1A		YC060-YC064
1001	22		X1	AA	22-8	SPARE	D40666P		20		D40460P	B01			YC067-YD157
1001Z				AA	0-0	SPARE	D40666P		19		D40460P	PERG	1F		YC067-YD157
1301	20		X1	EN	6-2	73-22-11	D40666P		11		D48114P	A06			YC051-YD158, YL951-YR328
1301Z				EN	0-0	73-22-11	D40666P			EN	D48114P	PERG	1F		YC051-YD158, YL951-YR328
2001B	24		Y2	GA	19-2	29-32-11	D40578P		13		D40498P	24			YC051-YD158, YL951-YR328
2001R	24		Y2	GA	0-0	29-32-11	D40578P		12		D40498P	23			YC051-YD158, YL951-YR328
2001Z				GA	0-0	29-32-11	D40578P		S/R		D40498P	22			YC051-YD158, YL951-YR328
2002B	24		7K	GB	11-10	34-49-11	D40680P		11		D40454P	A06			YC053-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5150

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Description Fam	FT-IN	Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W5156	286A5156			PSEU & AIR/GND SYS: M2061 & J22,J20 TO E/E BAY (ROUTE LEFT) (continued)											
2002W	24	7K	GB	0-0	34-49-11	D40680P	10				D40454P	A05			YC053-YD158, YL951-YR328
2002Z			GB	0-0	34-49-11	D40680P				GB	D40454P	PERG	1F		YC053-YD158, YL951-YR328
2003B	24	Y2	GC	11-10	34-49-11	D40680P	17				D40454P	B09			YC053-YD158, YL951-YR328
2003R	24	Y2	GC	0-0	34-49-11	D40680P	18				D40454P	B08			YC053-YD158, YL951-YR328
2003Z			GC	0-0	34-49-11	D40680P				GC	D40454P	PERG	1F		YC053-YD158, YL951-YR328
2004B	24	7K	GD	11-8	34-49-11	D40680P	21				D40458P	A02			YC053-YD158, YL951-YR328
2004W	24	7K	GD	0-0	34-49-11	D40680P	20				D40458P	A01			YC053-YD158, YL951-YR328
2004Z			GD	0-0	34-49-11	D40680P				GD	D40458P	PERG	1F		YC053-YD158, YL951-YR328
2011B	24	Y2	GK	12-8	34-61-18	D40642P	3				D40454P	B04			YC051-YC058
2011B	24	Y2	GK	12-8	31-32-15	D40642P	3				D40454P	B04			YC059-YD158, YL951-YR328
2011R	24	Y2	GK	0-0	34-61-18	D40642P	2				D40454P	A04			YC051-YC058
2011R	24	Y2	GK	0-0	31-32-15	D40642P	2				D40454P	A04			YC059-YD158, YL951-YR328
2011Z			GK	0-0	34-61-18	D40642P				GK	D40454P	PERG	1F		YC051-YC058
2011Z			GK	0-0	31-32-15	D40642P				GK	D40454P	PERG	1F		YC059-YD158, YL951-YR328
2012B	24	Y2	GL	24-3	73-24-12	D40642P	6				D40462P	B01			YC051-YC055
2012B	24	Y2	GL	24-0	73-24-12	D40642P	6				D40462P	B01			YC056-YD158, YL951-YR328
2012R	24	Y2	GL	0-0	73-24-12	D40642P	5				D40462P	B02			YC051-YD158, YL951-YR328
2012Z			GL	0-0	73-24-12	D40642P				GL	D40462P	PERG	1F		YC051-YD158, YL951-YR328
2013B	24	Y2	GM	24-1	73-24-12	D40642P	9				D40460P	B03			YC051-YC055
2013B	24	Y2	GM	23-10	73-24-12	D40642P	9				D40460P	B03			YC056-YD158, YL951-YR328
2013R	24	Y2	GM	0-0	73-24-12	D40642P	8				D40460P	B02			YC051-YD158, YL951-YR328
2013Z			GM	0-0	73-24-12	D40642P				GM	D40460P	PERG	1F		YC051-YD158, YL951-YR328

WIRE LIST
D280A108

91-21-11
Section W5150
Page 12
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5156	286A5156			PSEU & AIR/GND SYS: M2061 & J22,J20 TO E/E BAY (ROUTE LEFT) (continued)											
2201B	22	PB	KA		27-3	24-22-11	D11138	55			D40456P	J			YC051-YC055
2201B	22	PB	KA		26-11	24-22-11	D11138	55			D40456P	J			YC056-YD158, YL951-YR328
2201R	22	PB	KA		0-0	24-22-11	D11138	54			D40456P	K			YC051-YD158, YL951-YR328
2202B	22	PB	KB		21-1	24-28-41	D11138	32			D40454P	B02			YC051-YD158, YL951-YR328
2202R	22	PB	KB		0-0	24-28-41	D11138	31			D40454P	B01			YC051-YD158, YL951-YR328
2203B	22	PB	KC		32-10	31-53-11	D11142	8			D40462P	A20			YC051-YC055
2203B	22	PB	KC		32-6	31-53-11	D11142	8			D40462P	A20			YC056-YD158, YL951-YR328
2203R	22	PB	KC		0-0	31-53-11	D11142	20			D40462P	B20			YC051-YD158, YL951-YR328
2205B	20	HB	KE		14-6	32-64-11	D10982	19			TB0042K	C001	1		YC051-YD158, YL951-YR328
2205R	20	HB	KE		0-0	32-64-11	D10982	20			TB0042K	A001	1		YC051-YD158, YL951-YR328
2206B	20	HB	KF		18-6	32-64-11	D10982	2			TB0040K	C001	1		YC051-YD158, YL951-YR328
2206R	20	HB	KF		0-0	32-64-11	D10982	9			TB0040K	A001	1		YC051-YD158, YL951-YR328
2211B	22	PB	KK		33-0	32-64-11	D10982	55			D40462P	B04			YC051-YC055
2211B	22	PB	KK		32-9	32-64-11	D10982	55			D40462P	B04			YC056-YD158, YL951-YR328
2211R	22	PB	KK		0-0	32-64-11	D10982	33			D40462P	B05			YC051-YD158, YL951-YR328
2212B	22	PB	KL		33-0	32-64-11	D10982	57			D40462P	B06			YC051-YC055
2212B	22	PB	KL		32-9	32-64-11	D10982	57			D40462P	B06			YC056-YD158, YL951-YR328
2212R	22	PB	KL		0-0	32-64-11	D10982	58			D40462P	B07			YC051-YD158, YL951-YR328
2213B	22	PB	KM		33-0	32-64-11	D10982	12			D40462P	B08			YC051-YC055
2213B	22	PB	KM		32-9	32-64-11	D10982	12			D40462P	B08			YC056-YD158, YL951-YR328
2213R	22	PB	KM		0-0	32-64-11	D10982	11			D40462P	B09			YC051-YD158, YL951-YR328
2214B	22	PB	KN		33-0	32-64-11	D10982	46			D40462P	B10			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5150

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description		From	To								
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5156	286A5156			PSEU & AIR/GND SYS: M2061 & J22,J20 TO E/E BAY (ROUTE LEFT) (continued)											
2214B	22	PB	KN		32-9	32-64-11	D10982	46			D40462P	B10			YC056-YD158, YL951-YR328
2214R	22	PB	KN		0-0	32-64-11	D10982	45			D40462P	B11			YC051-YD158, YL951-YR328
2215B	22	X2	KP		24-2	32-41-11	D40498P	20			D40594P	B08			YC051-YC055
2215B	22	X2	KP		23-11	32-41-11	D40498P	20			D40594P	B08			YC056-YD158, YL951-YR328
2215R	22	X2	KP		0-0	32-41-11	D40498P	19			D40594P	B07			YC051-YD158, YL951-YR328
2215Z			KP		0-0	32-41-11	D40498P	21			D40594P	B09			YC051-YD158, YL951-YR328
2226B	20	HB	LA		18-3	32-31-11	D11142	36			TB0040K	C002	1		YC051-YD158, YL951-YR328
2226R	20	HB	LA		0-0	32-31-11	D11142	60			TB0040K	A002	1		YC051-YD158, YL951-YR328
2232B	24	PL	LG		32-10	32-31-11	D11142	61			D40462P	B12			YC051-YC055
2232B	24	PL	LG		32-6	32-31-11	D11142	61			D40462P	B12			YC056-YD158, YL951-YR328
2232R	24	PL	LG		0-0	32-31-11	D11142	38			D40462P	B13			YC051-YD158, YL951-YR328
2240B	24	PL	LP		32-10	32-31-11	D11142	35			D40462P	B14			YC051-YC055
2240B	24	PL	LP		32-6	32-31-11	D11142	35			D40462P	B14			YC056-YD158, YL951-YR328
2240R	24	PL	LP		0-0	32-31-11	D11142	18			D40462P	B15			YC051-YD158, YL951-YR328
2601B	24	Y2	SA		6-2	73-21-11	D40666P	23			D48114P	B01			YC051-YD158, YL951-YR328
2601R	24	Y2	SA		0-0	73-21-11	D40666P	22			D48114P	A01			YC051-YD158, YL951-YR328
2601Z			SA		0-0	73-21-11	D40666P			SA	D48114P	PERG	1F		YC051-YD158, YL951-YR328
2604B	22	VX	SD		6-9	77-31-11	D40724P	A04			D40594P	A03			YC051-YC055
2604B	22	VX	SD		6-10	77-31-11	D40724P	A04			D40594P	A03			YC056-YD158, YL951-YR328
2604W	22	VX	SD		0-0	77-31-11	D40724P	B04			D40594P	B03			YC051-YD158, YL951-YR328
2604Z			SD		0-0	77-31-11	D40724P	A05			D40594P	A04			YC051-YD158, YL951-YR328
2608B	22	PB	SH		6-9	78-36-11	D40724P	A12			D40594P	A05			YC051-YC055

WIRE LIST
D280A108

91-21-11
Section W5150
Page 14
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5156	286A5156			PSEU & AIR/GND SYS: M2061 & J22,J20 TO E/E BAY (ROUTE LEFT) (continued)											
2608B	22	PB	SH		6-10	78-36-11	D40724P	A12			D40594P	A05			YC056-YD158, YL951-YR328
2608R	22	PB	SH		0-0	78-36-11	D40724P	B12			D40594P	B05			YC051-YD158, YL951-YR328
2609B	22	PB	SJ		6-9	78-36-11	D40724P	A13			D40594P	A06			YC051-YC055
2609B	22	PB	SJ		6-10	78-36-11	D40724P	A13			D40594P	A06			YC056-YD158, YL951-YR328
2609R	22	PB	SJ		0-0	78-36-11	D40724P	B13			D40594P	B06			YC051-YD158, YL951-YR328
2610B	24	Y2	SK		22-8	73-24-11	D40724P	A14			D40452P	B05			YC051-YC055
2610B	24	Y2	SK		22-7	73-24-11	D40724P	A14			D40452P	B05			YC056-YD158, YL951-YR328
2610R	24	Y2	SK		0-0	73-24-11	D40724P	B14			D40452P	B06			YC051-YD158, YL951-YR328
2610Z			SK		0-0	73-24-11	D40724P	PERG	1F		D40452P	PERG	1F		YC051-YD158, YL951-YR328
2613B	24	Y2	SN		7-2	73-24-11	D40724P	A09			D40460P	B05			YC051-YC055
2613B	24	Y2	SN		7-3	73-24-11	D40724P	A09			D40460P	B05			YC056-YD158, YL951-YR328
2613R	24	Y2	SN		0-0	73-24-11	D40724P	B09			D40460P	B06			YC051-YD158, YL951-YR328
2613Z			SN		0-0	73-24-11	D40724P	PERG	1F		D40460P	PERG	1F		YC051-YD158, YL951-YR328
5501	24	PK			27-3	21-51-14	D11138	27			D40456P	B05			YC051-YC055
5501	24	PK			26-11	21-51-14	D11138	27			D40456P	B05			YC056-YD158, YL951-YR328
5502	20	PA			17-10	30-71-11	D40456P	B01			D40676P	10			YC051-YC055
5502	20	PA			17-7	30-71-11	D40456P	B01			D40676P	10			YC056-YD158, YL951-YR328
5508	22	CQ			20-4	21-27-21	D00164	1			D40576P	23			YC051-YC059, YC065-YD158
5508	22	CQ			20-4	21-27-21	D00164	1			SP00480		9		YC060-YC064
5508	22	CQ			16-11	21-27-21	D00164	1			D48112P	B10			YL951-YR328
5510	20	CQ			2-5	21-27-21	D00164	3			GD01753	DC..	E		YC051-YD158, YL951-YR328
5511	20	PA			2-4	21-27-21	D00164	4			GD00434	ST..	E		YC051-YD158, YL951-YR328
5512	20	PA			15-2	33-18-11	D00164	7			D46116P	30			YC051-YC065

WIRE LIST

D280A108

91-21-11

Section W5150

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W5156	286A5156				PSEU & AIR/GND SYS: M2061 & J22,J20 TO E/E BAY (ROUTE LEFT) (continued)											
5512	20		PA		15-3	33-18-11		D00164		7		D46116P		30		YC067-YD158, YL951-YR328
5513	22		PA		16-11	34-21-16		D00164		8		D48114P		A07		YC051-YD158, YL951-YR328
5514	22		CQ		16-11	21-27-21		D00164		9		D48112P		A01		YC051-YD158, YL951-YR328
5515	22		PA		11-3	34-21-16		D40454P		B03		D48112P		B04		YC051-YD158, YL951-YR328
5519	24		PK		6-4	21-42-11		D40676P		13		D48112P		B01		YC051-YD158, YL951-YR328
5520	24		PK		17-9	21-42-11		D40670P		23		D40456P		B06		YC051-YC055
5520	24		PK		17-5	21-42-11		D40670P		23		D40456P		B06		YC056-YD158, YL951-YR328
5521	24		PK		17-9	21-42-11		D40670P		24		D40456P		B07		YC051-YC055
5521	24		PK		17-5	21-42-11		D40670P		24		D40456P		B07		YC056-YD158, YL951-YR328
5522	24		PK		27-3	21-31-24		D40456P		B08		D11138		12		YC051-YC055
5522	24		PK		26-11	21-31-24		D40456P		B08		D11138		12		YC056-YD158, YL951-YR328
5527	20		PA		8-3	30-71-11		D40576P		17		D40666P		13		YC051-YD158, YL951-YR328
5528	20		PA		8-3	30-71-11		D40576P		19		D40666P		10		YC051-YD158, YL951-YR328
5529	22		PA		21-6	21-25-11		D40670P		32		D40724P		A15		YL951-YR328
5530	22		PA		21-6	21-25-11		D40670P		33		D40724P		A16		YL951-YR328
5531	22		CQ		16-11	21-27-21		D48112P		A10		D00164		6		YL951-YR328
5532	22		CQ		8-0	21-27-21		D40576P		23		SP00480		9		YC060-YC064
5532	22		CQ		8-1	21-27-21		D40576P		23		D48114P		A08		YL951-YR328
5533	22		CQ		27-10	31-53-11		D46116P		5		TB0501Y		A015	1A	YC060-YC064
6001R	20		PH		27-5	26-11-31		D11142		53		D40456P		H		YC051-YC055
6001R	20		PH		27-1	26-11-31		D11142		53		D40456P		H		YC056-YD158, YL951-YR328
6002R	20		PH		3-8	26-11-31		D11142		54		GD00044		DC..	1	YC051-YD158, YL951-YR328
6003	20		CQ		8-3	73-22-11		D40666P		14		D40576P		11		YC051-YD158, YL951-YR328
6004	24		PK		23-0	73-22-31		D40460P		A03		D40670P		25		YC051-YC055
6004	24		PK		22-9	73-22-31		D40460P		A03		D40670P		25		YC056-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5150

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5156	286A5156			PSEU & AIR/GND SYS: M2061 & J22,J20 TO E/E BAY (ROUTE LEFT) (continued)											
6005	24		B6		8-3	73-22-31	D40576P				D40666P				YC051-YD158, YL951-YR328
6006	24		PK		17-9	73-22-31	D40456P		B09		D40670P				YC051-YC055
6006	24		PK		17-5	73-22-31	D40456P		B09		D40670P				YC056-YD158, YL951-YR328
6007	24		PK		32-6	73-23-11	D11138				D40460P		A04		YC051-YC055
6007	24		PK		32-3	73-23-11	D11138				D40460P		A04		YC056-YD158, YL951-YR328
6008	24		PK		32-8	73-23-11	D11142			3	D40460P		A05		YC051-YC055
6008	24		PK		32-4	73-23-11	D11142			3	D40460P		A05		YC056-YD158, YL951-YR328
6009	24		B6		8-3	76-21-11	D40576P				D40666P			16	YC051-YD158, YL951-YR328
6010	24		B6		6-2	76-21-11	D40666P				D48114P		A02		YC051-YD158, YL951-YR328
6011	24		B6		6-2	76-21-11	D40666P				D48114P		B02		YC051-YD158, YL951-YR328
6012	24		B6		23-0	76-21-11	D40670P			27	D40460P		A06		YC051-YC055
6012	24		B6		22-9	76-21-11	D40670P			27	D40460P		A06		YC056-YD158, YL951-YR328
6014	20		PA		11-8	78-34-11	D40676P				D40454P		A10		YC051-YD158, YL951-YR328
6015	22		PA		14-7	30-11-11	D11142				D48112P		A03		YC051-YD158, YL951-YR328
6016	22		PA		14-5	30-11-11	D11138				D48112P		B03		YC051-YD158, YL951-YR328
6017	24		PK		22-11	73-22-11	D40460P		A07		D40666P			7	YC051-YC055
6017	24		PK		22-8	73-22-11	D40460P		A07		D40666P			7	YC056-YD158, YL951-YR328
6018R	20		PH		23-2	26-21-11	D40498P			13	D40724P		A18		YC051-YC055
6018R	20		PH		23-1	26-21-11	D40498P			13	D40724P		A18		YC056-YD158, YL951-YR328
6019R	20		PH		23-2	26-21-11	D40498P			14	D40724P		A19		YC051-YC055
6019R	20		PH		23-1	26-21-11	D40498P			14	D40724P		A19		YC056-YD158, YL951-YR328
6020R	20		PH		23-2	26-21-11	D40498P			15	D40724P		A20		YC051-YC055
6020R	20		PH		23-1	26-21-11	D40498P			15	D40724P		A20		YC056-YD158, YL951-YR328
6021R	20		PH		23-2	26-21-11	D40498P			26	D40724P		B18		YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5150

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W5156	286A5156				PSEU & AIR/GND SYS: M2061 & J22,J20 TO E/E BAY (ROUTE LEFT) (continued)											
6021R	20		PH		23-1	26-21-11		D40498P	26			D40724P	B18		YC056-YD158, YL951-YR328	
6022R	20		PH		23-2	26-21-11		D40498P	27			D40724P	B19		YC051-YC055	
6022R	20		PH		23-1	26-21-11		D40498P	27			D40724P	B19		YC056-YD158, YL951-YR328	
6023R	20		PH		23-2	26-21-11		D40498P	28			D40724P	B20		YC051-YC055	
6023R	20		PH		23-1	26-21-11		D40498P	28			D40724P	B20		YC056-YD158, YL951-YR328	
6024	20		CQ		8-1	74-11-11		D40576P	7			D48114P	B03		YC051-YD158, YL951-YR328	
6025R	22		PH		21-7	SPARE		D40724P	B17			D40670P	20		YC051-YC055	
6025R	22		PH		21-6	SPARE		D40724P	B17			D40670P	20		YC056-YD158, YL951-YR328	
FRB1					0-0	34-49-11		D40680P			GB	D40680P	S/R		YC053-YD158, YL951-YR328	
FRC1					0-0	34-49-11		D40680P			GC	D40680P	S/R		YC053-YD158, YL951-YR328	
FRD1					0-0	34-49-11		D40680P			GD	D40680P	S/R		YC053-YD158, YL951-YR328	
FREA					0-0	73-22-11		D40666P			EN	D40666P	12		YC051-YD158, YL951-YR328	
FREB					0-0	73-22-11		D40666P			EN	D40666P	S/R		YC051-YD158, YL951-YR328	
FRGA					0-0	34-61-18		D40642P			GK	D40642P	4		YC051-YC058	
FRGA					0-0	31-32-15		D40642P			GK	D40642P	4		YC059-YD158, YL951-YR328	
FRGB					0-0	34-61-18		D40642P			GK	D40642P	S/R		YC051-YC058	
FRGB					0-0	31-32-15		D40642P			GK	D40642P	S/R		YC059-YD158, YL951-YR328	
FRGC					0-0	73-24-12		D40642P			GL	D40642P	7		YC051-YD158, YL951-YR328	
FRGD					0-0	73-24-12		D40642P			GL	D40642P	S/R		YC051-YD158, YL951-YR328	
FRGE					0-0	73-24-12		D40642P			GM	D40642P	10		YC051-YD158, YL951-YR328	
FRGF					0-0	73-24-12		D40642P			GM	D40642P	S/R		YC051-YD158, YL951-YR328	
FRSA					0-0	73-21-11		D40666P			SA	D40666P	24		YC051-YD158, YL951-YR328	

WIRE LIST

D280A108

91-21-11

Section W5150

Page 18

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5156 286A5156 PSEU & AIR/GND SYS: M2061 & J22,J20 TO E/E BAY (ROUTE LEFT) (continued)																
FRSB						0-0	73-21-11	D40666P			SA	D40666P	S/R			YC051-YD158, YL951-YR328
FRVX						0-0	34-49-11	D40680P	12			D40680P			GB	YC053-YD158, YL951-YR328
FRVY						0-0	34-49-11	D40680P	16			D40680P			GC	YC053-YD158, YL951-YR328
FRVZ						0-0	34-49-11	D40680P	19			D40680P			GD	YC053-YD158, YL951-YR328
W5158 286A5158 PSEU & AIR/GND SYS: M2061 & J24,J20 TO E/E BAY (ROUTE RIGHT)																
0001	22	PA				25-8	35-11-11	D40490J	14			D00438	1			YC051-YC055
0001	22	PA				26-2	35-11-11	D40490J	14			D00438	1			YC056-YR328
0002	20	PA				7-9	35-11-11	D00438	2			GD01008	DC..	1A		YC051-YC055
0002	20	PA				8-1	35-11-11	D00438	2			GD01008	DC..	1A		YC056-YR328
0003	22	PA				25-8	35-11-11	D40490J	13			D00438	3			YC051-YC055
0003	22	PA				26-2	35-11-11	D40490J	13			D00438	3			YC056-YR328
0004	22	PA				10-5	78-32-61	D40700P	5			D46120P	A07			YC051-YC055
0004	22	PA				10-0	78-32-61	D40700P	5			D46120P	A07			YC056-YR328
0005	22	PA				10-5	78-32-61	D40700P	7			D46120P	B07			YC051-YC055
0005	22	PA				10-0	78-32-61	D40700P	7			D46120P	B07			YC056-YR328
0006	22	PA				24-1	78-32-61	D40700P	17			D40486P	A05			YC051-YC055
0006	22	PA				24-6	78-32-61	D40700P	17			D40486P	A05			YC056-YR328
0007	22	PA				24-1	78-32-61	D40700P	9			D40486P	A06			YC051-YC055
0007	22	PA				24-6	78-32-61	D40700P	9			D40486P	A06			YC056-YR328
0008	22	PA				17-8	SPARE	D11140	8			TB1808X	B003	1A		YC051-YD158, YN231-YN501
0008	22	PA				17-8	52-61-11	D11140	8			TB1808X	B003	1A		YL951-YL999, YR301-YR328
0009	20	PA				9-8	52-71-14	D40702P	20			D40750P	16			ALL
0010	20	CQ				10-5	52-71-14	D40700P	22			D46120P	B09			YC051-YC055
0010	20	CQ				10-0	52-71-14	D40700P	22			D46120P	B09			YC056-YR328
0011	20	PA				12-7	52-71-14	D40700P	23			D48116P	B09			YC051-YL999, YN232-YR328
0011	20	CQ				12-7	52-71-14	D40700P	23			D48116P	B09			YN231
0012	20	PA				12-7	52-71-14	D40700P	24			D48116P	B07			ALL
0013	20	PA				12-7	52-71-14	D40700P	25			D48116P	B08			ALL
0014	20	PA				10-5	52-71-14	D40700P	26			D46120P	B10			YC051-YC055
0014	20	PA				10-0	52-71-14	D40700P	26			D46120P	B10			YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W5150

Page 19

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number		Description		From				To				Effectivity	
	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type		Splice
W5158	286A5158		PSEU & AIR/GND SYS: M2061 & J24,J20 TO E/E BAY (ROUTE RIGHT) (continued)											
0015	22	PA		17-11	SPARE	D40490J		4		D40638P		12		YC067-YL999, YN232-YR328
0020	24	GK		26-7	21-31-23	D41830P		B08		D40884P		12		YC053, YC055
0020	24	PK		35-0	21-31-23	D41830P		B08		D40884P		12		YC060-YC064
0020	24	PK		26-7	21-31-23	D40618P		A06		D40884P		12		YC067-YR328
0021	24	GK		27-7	21-31-23	D41830P		B09		D40884P		13		YC053, YC055
0021	24	PK		35-0	21-31-23	D41830P		B09		D40884P		13		YC060-YC064
0021	24	PK		26-7	21-31-23	D40618P		A07		D40884P		13		YC067-YR328
0022	20	CQ		24-1	21-31-23	D41830P		B10		D40884P		14		YC053, YC055
0022	20	CQ		35-0	21-31-23	D41830P		B10		D40884P		14		YC060-YC064
0022	20	CQ		26-7	21-31-23	D40618P		A08		D40884P		14		YC067-YR328
0030	22	PA		9-3	31-31-15	D40618P		B02		D40426P		5		YC065-YR328
0031	22	GA		24-1	26-16-21	D40884P		15		D40638P		13		YC053, YC055
0031	22	PA		17-0	26-16-21	D40884P		15		D40638P		13		YC060-YC064
0031	22	PA		24-1	26-16-21	D40884P		15		D40638P		13		YC067-YR328
0032	22	PA		28-7	26-16-21	D40640P		12		D40486P		B05		YC067-YR328
0034	22	PA		6-0	SPARE	D40884P		29		D40488P		7		YD158
0035	22	PA		6-0	SPARE	D40884P		30		D40488P		8		YD158
0036	22	PA		6-0	SPARE	D40884P		31		D40488P		9		YD158
0037	18	PA		10-10	25-29-11	SM00004		S		GD01008		AC..	1D	YL951-YL999, YN232-YR328
0040	20	CQ		9-6	23-32-14	D40750P		11		D40700P		15		YD158, YL951-YN260
0040	20	CQ		9-6	44-21-22	D40750P		11		D40700P		15		YN501-YR328
0041	18	PA		20-8	25-29-11	D40750P		31	18	D13900		1		YL951-YL999, YN232-YR328
0043	18	PA		11-4	25-29-11	D13900		6		GD01008		ST..	1D	YL951-YL999, YN232-YR328
0044	18	PA		11-4	25-29-11	D13900		7		GD01008		ST..	1D	YL951-YL999, YN232-YR328
0048	18	PA		1-0	25-29-11	D13900		5		SM00004		S		YL951-YL999, YN232-YR328
0049	18	PA		1-0	25-29-11	D13900		4		SM00004		S		YL951-YL999, YN232-YR328
0101	20	PA		21-1	28-23-11	D40750P		26		D40858P		1		YD158-YR328
0102	20	PA		21-1	28-23-11	D40750P		27		D40858P		2		YD158-YR328
0103	20	PA		21-1	28-23-11	D40750P		28		D40858P		3		YD158-YR328
0104	20	PA		22-6	28-23-11	D46120P		B08		D40858P		4		YD158-YR328
0105	20	PA		22-6	28-23-11	D46120P		A09		D40858P		5		YD158-YR328
0106	20	PA		22-6	28-23-11	D46120P		A08		D40858P		6		YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W5150

Page 20

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5158	286A5158			PSEU & AIR/GND SYS: M2061 & J24,J20 TO E/E BAY (ROUTE RIGHT) (continued)											
0108	20		PA		15-3	28-23-11	D40858P		9		D40490J		5		YD160-YR328
0109	20		PA		15-3	28-23-11	D40858P		8		D40490J		12		YD160-YR328
0110	20		PA		22-6	28-23-11	D46120P		B05		D40858P		7		YD160-YR328
0203	22		PA		24-9	27-62-11	D40638P		10		D40484P		B10		YL953-YL999, YR301-YR328
0204	22		PA		24-9	27-62-11	D40638P		11		D40484P		A03		YL953-YL999, YR301-YR328
0213	22		PA		29-7	23-42-11	D40858P		29		D40484P		B07		YL951-YR328
0214	22		PA		29-7	23-42-11	D40858P		31		D40484P		B10		YL951-YL952, YN231-YN501
0214	22		PA		29-10	23-42-11	D40858P		31		D40618P		B10		YL953-YL999, YR301-YR328
0215	22		PA		23-9	23-42-11	D40858P		30		TB0608X		B003	1A	YL951-YL999, YN232-YR328
0215	22		PA		23-8	23-42-11	D40858P		30		TB0608X		B003	1A	YN231
0216	22		PA		29-7	23-42-11	D40858P		28		D40484P		A03		YL951-YL952, YN231-YN501
0216	22		PA		29-10	23-42-11	D40858P		28		D40618P		B09		YL953-YL999, YR301-YR328
0301	20		PA		5-0	31-31-15	D11140		30		GD00034		DC..	1	YL955-YL999, YN236-YR328
0501	20		CQ		18-11	22-11-12	D11140		46		D40490J		18		ALL
0502	20		CQ		18-11	22-11-12	D11140		47		D40490J		19		ALL
0503	22		PA		11-0	31-31-11	D40700P		1		D11140		54		ALL
0504	22		PA		11-0	31-31-15	D11140		51		D40700P		2		ALL
0505	22		PA		29-5	31-31-15	D11140		29		D40426P		2		YC051-YC055
0505	22		PA		29-9	31-31-15	D11140		29		D40426P		2		YC056-YR328
0506	22		PA		29-5	31-31-15	D11140		45		D40426P		3		YC051-YC055
0506	22		PA		29-9	31-31-15	D11140		45		D40426P		3		YC056-YR328
0509	22		CQ		18-11	34-31-21	D11140		5		D40490J		7		ALL
0510	22		PA		29-3	34-33-21	D11140		55		D40486P		A01		YC051-YC055
0510	22		PA		29-7	34-33-21	D11140		55		D40486P		A01		YC056-YR328
0511	22		CQ		24-10	27-62-11	D40634P		28		D40484P		A10		YC051-YC055
0511	22		CQ		24-8	27-62-11	D40634P		28		D40484P		A10		YC056-YR328
0512	22		PA		24-10	23-32-14	D40426P		6		D40702P		18		YD158, YL951-YN260
0512	22		PA		24-10	44-21-22	D40426P		6		D40702P		18		YN501-YR328
0513	22		CQ		18-11	34-51-21	D11140		15		D40490J		8		ALL
0514	22		PA		15-4	34-53-21	D46100P		4		D11140		26		YC051-YC055
0514	22		PA		14-11	34-53-21	D46100P		4		D11140		26		YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W5150

Page 21

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number		Fam	Description		From			To			Effectivity			
	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice	
W5158	286A5158			PSEU & AIR/GND SYS: M2061 & J24,J20 TO E/E BAY (ROUTE RIGHT) (continued)											
0515	22	PA		16-7	34-55-21	D11140		32		TB0606Y	A005	1A		YC051-YC055	
0515	22	PA		16-3	34-55-21	D11140		32		TB0606Y	A005	1A		YC056-YL999, YN232-YR328	
0515	22	PA		16-4	34-55-21	D11140		32		TB0606Y	A005	1A		YN231	
0516	22	PA		29-3	34-57-21	D11140		16		D40486P	A02			YC051-YC055	
0516	22	PA		29-7	34-57-21	D11140		16		D40486P	A02			YC056-YR328	
0517	22	PA		18-11	34-21-21	D11140		53		D40490J	17			ALL	
0518	22	CQ		15-4	29-23-11	D11140		7		D46100P	32			YC051-YC055	
0518	22	CQ		14-11	29-23-11	D11140		7		D46100P	32			YC056-YR328	
0519	20	CQ		26-1	29-23-11	D11140		2		D40484P	H			ALL	
0520	22	PA		29-5	31-31-15	D11140		25		D40426P	1			YC051-YC055	
0520	22	PA		29-9	31-31-15	D11140		25		D40426P	1			YC056-YR328	
0521	22	PA		10-4	32-44-11	D40702P		1		D46100P	11			YC051-YC055	
0521	22	PA		10-0	32-44-11	D40702P		1		D46100P	11			YC056-YR328	
0522	22	PA		10-4	32-44-11	D40702P		2		D46100P	12			YC051-YC055	
0522	22	PA		10-0	32-44-11	D40702P		2		D46100P	12			YC056-YR328	
0523	22	PA		10-4	32-44-11	D40702P		3		D46100P	13			YC051-YC055	
0523	22	PA		10-0	32-44-11	D40702P		3		D46100P	13			YC056-YR328	
0524	22	PA		20-1	32-44-11	D40488P		1		D40702P	4			ALL	
0525	22	PA		29-9	31-31-15	D40488P		13		D40486P	A04			YC051-YC055	
0525	22	PA		30-2	31-31-15	D40488P		13		D40486P	A04			YC056-YR328	
0527	20	PA		23-4	29-11-11	D46120P		A01		D40486P	A09			YC051-YC055	
0527	20	PA		23-9	29-11-11	D46120P		A01		D40486P	A09			YC056-YR328	
0528	20	PA		23-4	29-11-11	D46120P		B01		D40486P	A10			YC051-YC055	
0528	20	PA		23-9	29-11-11	D46120P		B01		D40486P	A10			YC056-YR328	
0529	20	PA		20-3	28-21-11	D46120P		A05		D40618P	A02			YC051-YC055	
0529	20	PA		20-1	28-21-11	D46120P		A05		D40618P	A02			YC056-YR328	
0530	20	PA		12-7	52-71-14	D40700P		27		D48116P	B05			YC051-YL999, YR301-YR328	
0531	18	PA		14-4	24-11-21	D40638P		4		D46100P	21			YC051-YC055	
0531	18	PA		14-0	24-11-21	D40638P		4		D46100P	21			YC056-YR328	
0532	18	PA		25-2	24-11-21	D40638P		5		D40618P	F			YC051-YC055	
0532	18	PA		25-0	24-11-21	D40638P		5		D40618P	F			YC056-YR328	
0533	20	PA		24-11	27-23-11	D40484P		B05		D40638P	7			ALL	
0534	20	PA		24-11	27-23-11	D40484P		B06		D40638P	8			ALL	
0536	22	PA		13-8	32-51-11	D40638P		1		D40750P	7			YC051-YC055	
0536	22	PA		13-7	32-51-11	D40638P		1		D40750P	7			YC056-YR328	
0537	22	CQ		24-10	27-62-11	D40634P		7		D40484P	A04			YC051-YC055	
0537	22	CQ		24-8	27-62-11	D40634P		7		D40484P	A04			YC056-YR328	

WIRE LIST

D280A108

91-21-11

Section W5150

Page 22

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5158							PSEU & AIR/GND SYS: M2061 & J24,J20 TO E/E BAY (ROUTE RIGHT) (continued)								
I	0538	22		CQ	24-10	27-62-11	D40634P		8		D40484P	A05			YC051-YC055
I	0538	22		CQ	24-8	27-62-11	D40634P		8		D40484P	A05			YC056-YR328
I	0539	22		CQ	24-10	27-62-11	D40634P		9		D40484P	A06			YC051-YC055
I	0539	22		CQ	24-8	27-62-11	D40634P		9		D40484P	A06			YC056-YR328
I	0540	22		CQ	24-10	27-62-11	D40634P		10		D40484P	A07			YC051-YC055
I	0540	22		CQ	24-8	27-62-11	D40634P		10		D40484P	A07			YC056-YR328
I	0541	22		CQ	24-10	27-62-11	D40634P		11		D40484P	B04			YC051-YC055
I	0541	22		CQ	24-8	27-62-11	D40634P		11		D40484P	B04			YC056-YR328
I	0542	20		CQ	20-3	22-11-12	D40484P		B01		D40490J	10			YC051-YC055
I	0542	20		CQ	20-2	22-11-12	D40484P		B01		D40490J	10			YC056-YR328
I	0543	20		CQ	20-3	22-11-12	D40484P		B02		D40490J	11			YC051-YC055
I	0543	20		CQ	20-2	22-11-12	D40484P		B02		D40490J	11			YC056-YR328
I	0544	20		CQ	20-3	22-11-11	D40484P		B03		D40490J	2			YC051-YC055
I	0544	20		CQ	20-2	22-11-11	D40484P		B03		D40490J	2			YC056-YR328
I	0545	20		CQ	24-8	SPARE	D40702P		CAP	Y	D40426P	8			YC051-YC052
I	0545	20		CQ	24-6	SPARE	D40702P		13		D40426P	8			YC053-YC055
I	0545	20		CQ	24-10	SPARE	D40702P		13		D40426P	8			YC056-YD158
I	0545	20		CQ	24-10	23-34-01	D40702P		13		D40426P	8			YL951-YN260
I	0545	20		CQ	10-0	44-21-26	D40702P		13		D46100P	17			YN501-YR328
I	0546	22		PA	10-4	23-34-01	D40702P		14		D46100P	7			YC051-YC055
I	0546	22		PA	10-0	23-34-01	D40702P		14		D46100P	7			YC056-YD158, YN231
I	0546	22		CQ	10-0	23-34-01	D40702P		14		D46100P	7			YL951-YL999, YN232-YN260
I	0546	22		CQ	10-0	44-21-26	D40702P		30		D46100P	25			YN501-YR328
I	0547	22		PA	10-4	23-34-01	D40702P		15		D46100P	8			YC051-YC055
I	0547	22		PA	10-0	23-34-01	D40702P		15		D46100P	8			YC056-YD158, YN231
I	0547	22		CQ	10-0	23-34-01	D40702P		15		D46100P	8			YL951-YL999, YN232-YN260
I	0547	22		PA	10-0	44-21-26	D40702P		15		D46100P	8			YN501-YR328
I	0548	22		CQ	14-4	29-25-11	D46100P		33		D40640P	5			YC051-YC055
I	0548	22		CQ	13-11	29-25-11	D46100P		33		D40640P	5			YC056-YR328
I	0549	18		CQ	24-11	29-25-11	D40640P		6		D40484P	F			ALL
I	0550	18		CQ	24-11	29-25-11	D40640P		7		D40484P	G			ALL
I	0551	22		PA	24-9	21-43-21	D11880		1		D40702P	17			YC051-YC055
I	0551	22		PA	24-11	21-43-21	D11880		1		D40702P	17			YC056-YR328
I	0552	22		PA	24-9	21-43-21	D11880		2		D40702P	16			YC051-YC055
I	0552	22		PA	24-11	21-43-21	D11880		2		D40702P	16			YC056-YR328
I	0553	20		PA	7-7	21-43-21	D11880		3		GD01008	DC..	1A		ALL
I	0554	20		PA	7-7	21-31-24	D11880		4		GD01008	DC..	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W5150

Page 23

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W5158	286A5158				PSEU & AIR/GND SYS: M2061 & J24,J20 TO E/E BAY (ROUTE RIGHT) (continued)											
0555	22	PA		22-3	21-31-24	D11880		12			D40484P	B08		YC051-YC055		
0555	22	PA		22-2	21-31-24	D11880		12			D40484P	B08		YC056-YR328		
0556	20	PA		7-7	21-43-21	D11880		6			GD01008	ST..	1A	ALL		
0557	20	PA		12-10	78-34-21	D40634P		25			D40700P	6		ALL		
0558	20	CQ		14-3	27-62-11	D40634P		26			D46100P	38		YC051-YC055		
0558	20	CQ		13-11	27-62-11	D40634P		26			D46100P	38		YC056-YR328		
0559	20	CQ		14-3	27-62-11	D40634P		27			D46100P	39		YC051-YC055		
0559	20	CQ		13-11	27-62-11	D40634P		27			D46100P	39		YC056-YR328		
0560	22	PA		25-0	32-42-11	D40488P		2			D11140	48		ALL		
0561	22	PA		25-0	32-42-11	D40488P		3			D11140	49		ALL		
0562	24	PK		9-4	21-43-21	D40692P		12			D40750P	19		ALL		
0563	24	PK		10-3	21-43-21	D40692P		11			D46120P	A02		YC051-YC055		
0563	24	PK		9-10	21-43-21	D40692P		11			D46120P	A02		YC056-YR328		
0564	24	PK		10-3	21-43-21	D40692P		10			D46120P	B02		YC051-YC055		
0564	24	PK		9-10	21-43-21	D40692P		10			D46120P	B02		YC056-YC059, YC065-YR328		
0564	24	PK		9-10	21-43-21	D40692P		CAP	Y		D46120P	B02		YC060-YC064		
0565	24	PK		10-3	21-43-21	D40692P		3			D46120P	A03		YC051-YC055		
0565	24	PK		9-10	21-43-21	D40692P		3			D46120P	A03		YC056-YC059, YC065-YD158		
0566	24	PK		10-3	21-43-21	D40692P		1			D46120P	B03		YC051-YC055		
0566	24	PK		9-10	21-43-21	D40692P		1			D46120P	B03		YC056-YR328		
0569	22	CQ		2-6	21-27-31	D48116P		B10			D40634P	17		ALL		
0574	22	PA		15-4	32-64-21	D11140		19			D46100P	3		YC051-YC055		
0574	22	PA		14-11	32-64-21	D11140		19			D46100P	3		YC056-YR328		
0576	22	PA		14-3	21-27-31	D40634P		12			D46100P	6		YC051-YC055		
0576	22	PA		13-11	21-27-31	D40634P		12			D46100P	6		YC056-YR328		
0577	22	PA		24-10	21-27-31	D40634P		13			D40484P	A08		YC051-YC055		
0577	22	PA		24-8	21-27-31	D40634P		13			D40484P	A08		YC056-YR328		
0579	22	CQ		2-6	21-27-31	D40638P		6			D48116P	A01		ALL		
0580	22	CQ		2-6	21-27-31	D40638P		9			D48116P	B01		ALL		
0581	22	CQ		11-2	32-31-12	D11140		24			D40702P	9		ALL		
0582	22	CQ		3-5	32-31-12	D11140		44			SM00001		S	ALL		
0583	22	CQ		3-5	32-31-12	D11140		23			SM00001		S	ALL		
0584	22	CQ		8-4	32-31-12	SM00001			S		D40702P	10		ALL		
0585	22	CQ		3-5	32-31-12	D11140		9			SM00002		S	ALL		
0586	22	CQ		3-5	32-31-12	D11140		20			SM00002		S	ALL		
0587	22	CQ		8-4	32-31-12	SM00002			S		D40702P	11		ALL		
0588	22	CQ		11-2	32-31-12	D11140		43			D40702P	12		ALL		

WIRE LIST

D280A108

91-21-11

Section W5150

Page 24

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To			Effectivity				
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type		Splice	Equip	Term	Type
W5158	286A5158			PSEU & AIR/GND SYS: M2061 & J24,J20 TO E/E BAY (ROUTE RIGHT) (continued)											
0589	22	PA			14-7	32-64-12	D11140	41			D40750P	8			ALL
0590	20	PA			5-0	32-64-12	D11140	61			GD00034	DC..	1		ALL
0597	24	PK			8-1	21-43-21	SP04602		9		D40692P	10			YC060-YC064
0601	22	PA			11-0	32-31-12	D11140	21			D40700P	3			ALL
0604	22	PA			11-0	32-31-12	D11140	39			D40700P	4			ALL
0609	20	PA			15-3	47-30-11	D40858P	19			D40490J	24			YD160-YR328
0610	22	PA			10-4	32-41-11	D40702P	5			D46100P	1			YC051-YC055
0610	22	PA			10-0	32-41-11	D40702P	5			D46100P	1			YC056-YR328
0611	22	PA			20-1	32-41-11	D40702P	6			D40488P	4			ALL
0612	22	PA			18-11	32-41-11	D40488P	17			D46100P	10			ALL
0621	22	PA			13-8	32-31-12	D40638P	3			D40750P	20			YC051-YC055
0621	22	PA			13-7	32-31-12	D40638P	3			D40750P	20			YC056-YR328
0622	24	PK			30-0	31-31-15	D40488P	5			D40426P	4			YC051-YC055
0622	24	PK			30-4	31-31-15	D40488P	5			D40426P	4			YC056-YR328
0627	20	PA			24-7	47-30-11	D40702P	31			D40486P	B08			YD160-YR328
0628	20	PA			24-4	47-30-11	D40692P	4			D40486P	B09			YD160-YR328
0629	20	PA			24-6	47-30-11	D40700P	30			D40486P	B10			YD160-YR328
0630	22	PA			24-0	23-31-06	D40488P	22			D40634P	30			YC051-YD158, YL951-YN260
0630	20	CQ			24-0	44-21-22	D40488P	22			D40634P	30			YN501
0630	20	PA			24-0	44-21-22	D40488P	22			D40634P	30			YR301-YR328
0631	22	PA			24-0	23-31-06	D40488P	23			D40634P	31			YC051-YD158, YL951-YN260
0631	22	PA			24-0	44-21-22	D40488P	23			D40634P	31			YN501-YR328
0633	20	PA			24-6	47-30-11	D40486P	A08			D40700P	31			YD160-YR328
0634	20	PA			24-3	SPARE	D40490J	21			D40426P	14			YD160-YL999, YN232-YR328
0634	20	PA			24-3	47-30-11	D40490J	21			D40426P	14			YN231
0635	20	PA			24-3	47-30-11	D40490J	23			D40426P	15			YD160-YR328
0636	20	PA			11-11	47-30-11	D40490J	22			D40884P	10			YD160-YR328
0637	20	PA			26-7	28-44-11	D40618P	B07			D40884P	6			YD160-YR328
0638	16	PA			15-3	47-30-11	D40858P	20	16		D40490J	20	16		YD160-YR328
0670	22	CQ			18-10	21-27-31	D03464	1			D48116P	A10			ALL
0671	20	CQ			2-5	21-27-31	D03464	3			GD00383	DC..	1A		ALL
0672	20	PA			2-5	21-27-31	D03464	4			GD00383	ST..	1A		ALL
0673	22	CQ			19-1	21-27-31	D03464	6			D40634P	19			ALL
0674	20	PA			16-8	33-18-11	D03464	7			D46120P	A04			YC051-YC055
0674	20	PA			16-3	33-18-11	D03464	7			D46120P	A04			YC056-YR328
0675	22	PA			18-10	34-21-16	D03464	8			D48116P	A04			ALL

WIRE LIST

D280A108

91-21-11

Section W5150

Page 25

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity			
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice	
W5158	286A5158				PSEU & AIR/GND SYS: M2061 & J24,J20 TO E/E BAY (ROUTE RIGHT) (continued)											
0676	22		CQ		16-5	21-27-31	D03464		9			D46100P	31			YC051-YC055
0676	22		CQ		16-1	21-27-31	D03464		9			D46100P	31			YC056-YR328
0677	20		CQ		2-5	21-27-31	D03464		11			GD00383	DC..	1A		ALL
0678	22		PA		2-6	SPARE	D40638P		14			D48116P	A03			ALL
0680	22		PA		2-6	SPARE	D40638P		2			D48116P	B04			ALL
0682	20		CQ		24-8	SPARE	D40702P		CAP	Y		D40426P	7			YC051-YC052
0682	20		CQ		24-6	SPARE	D40702P		21			D40426P	7			YC053-YC055
0682	20		CQ		24-10	SPARE	D40702P		21			D40426P	7			YC056-YR328
0684	22		PA		12-7	31-31-11	D40700P		8			D48116P	B03			ALL
0685	22		CQ		9-8	32-31-12	D40702P		24			D40750P	5			ALL
0686	22		PA		8-6	32-41-11	D40750P		2			D46100P	2			ALL
0687	20		PA		8-9	33-18-11	D40750P		9			D46120P	B04			ALL
0688	20		PA		20-0	33-36-11	D40618P		B04			D46100P	14			YC051-YC055
0688	20		PA		19-11	33-36-11	D40618P		B04			D46100P	14			YC056-YR328
0689	20		PA		20-0	33-36-12	D40618P		B05			D46100P	15			YC051-YC055
0689	20		PA		19-11	33-36-12	D40618P		B05			D46100P	15			YC056-YR328
0690	20		CQ		8-6	34-41-11	D40750P		4			D46100P	18			YC051-YC052
0690	20		CQ		8-6	SPARE	D40750P		4			D46100P	18			YC067-YR328
0691	22		PA		8-6	34-53-31	D40750P		1			D46100P	5			ALL
0692	20		PA		9-6	73-22-11	D40750P		3			D40700P	10			ALL
0693	20		CQ		9-8	23-34-01	D40750P		14			D40702P	22			YC051-YD158, YL951-YN260
0693	20		CQ		9-8	44-21-26	D40750P		14			D40702P	22			YN501-YR328
0694	20		CQ		9-8	23-34-01	D40750P		15			D40702P	23			YC051-YD157
0694	20		CQ		9-8	SPARE	D40750P		15			D40702P	23			YD158-YR328
0695	22		PA		8-6	SPARE	D40750P		6			D46100P	9			YC051-YC065
0695	22		PA		8-6	25-51-11	D40750P		6			D46100P	9			YC067-YR328
0696	22		PA		24-1	31-31-11	D40700P		21			D40486P	A07			YC051-YC055
0696	22		PA		24-6	31-31-11	D40700P		21			D40486P	A07			YC056-YR328
0697	22		PA		24-1	31-31-11	D40700P		20			D40486P	B07			YC051-YC055
0697	22		PA		24-6	31-31-11	D40700P		20			D40486P	B07			YC056-YR328
0706	20		PA		13-11	SPARE	D40640P		1			D46100P	24			YC067-YL999, YN232-YR328
0707	22		PA		13-3	SPARE	D40750P		10			TB1808X	A003	%A		YC067-YL999, YR301-YR328
1102	20		X1	BP	14-3	27-62-11	D40634P		22			D46100P	36			YC051-YC055
1102	20		X1	BP	13-11	27-62-11	D40634P		22			D46100P	36			YC056-YR328
1102Z				BP	0-0	27-62-11	D40634P		23			D46100P	37			ALL
1103	20		X1	BQ	24-10	27-62-11	D40634P		21			D40484P	A09			ALL

WIRE LIST

D280A108

91-21-11

Section W5150

Page 26

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From			To			Effectivity		
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W5158	286A5158			PSEU & AIR/GND SYS: M2061 & J24,J20 TO E/E BAY (ROUTE RIGHT) (continued)										
1103Z				BQ	0-0	27-62-11	D40634P	20			D40484P	B09		ALL
2001B	24	PL		GA	24-0	23-31-06	D40488P	14			D40634P	15		YC051-YD158, YL951-YN260
2001B	24	PL		GA	24-0	44-21-22	D40488P	14			D40634P	15		YN501-YR313
2001B	24	Y2		GA	24-0	44-21-22	D40488P	14			D40634P	15		YR314-YR328
2001R	24	PL		GA	0-0	23-31-06	D40488P	6			D40634P	14		YC051-YD158, YL951-YN260
2001R	24	PL		GA	0-0	44-21-22	D40488P	6			D40634P	14		YN501-YR313
2001R	24	Y2		GA	0-0	44-21-22	D40488P	6			D40634P	14		YR314-YR328
2001Z				GA	0-0	44-21-22	D40488P		GA		D40634P	DED		YR314-YR328
2002B	24	PL		GB	24-0	23-31-06	D40488P	19			D40634P	18		YC051-YD158, YL951-YN260
2002B	24	PL		GB	24-0	44-21-22	D40488P	19			D40634P	18		YN501-YR313
2002B	24	Y2		GB	24-0	44-21-22	D40488P	19			D40634P	18		YR314-YR328
2002R	24	PL		GB	0-0	23-31-06	D40488P	18			D40634P	16		YC051-YD158, YL951-YN260
2002R	24	PL		GB	0-0	44-21-22	D40488P	18			D40634P	16		YN501-YR313
2002R	24	Y2		GB	0-0	44-21-22	D40488P	18			D40634P	16		YR314-YR328
2002Z				GB	0-0	44-21-22	D40488P		GA		D40634P	DED		YR314-YR328
2003B	24	PL		GC	24-0	23-31-06	D40488P	21			D40634P	29		YC051-YD158, YL951-YN260
2003B	24	PL		GC	24-0	44-21-22	D40488P	21			D40634P	29		YN501-YR313
2003B	24	Y2		GC	24-0	44-21-22	D40488P	21			D40634P	29		YR314-YR328
2003R	24	PL		GC	0-0	23-31-06	D40488P	20			D40634P	24		YC051-YD158, YL951-YN260
2003R	24	PL		GC	0-0	44-21-22	D40488P	20			D40634P	24		YN501-YR313
2003R	24	Y2		GC	0-0	44-21-22	D40488P	20			D40634P	24		YR314-YR328
2003Z				GC	0-0	44-21-22	D40488P		GA		D40634P	DED		YR314-YR328
2201B	22	X2		KA	24-10	28-41-11	D40618P	A04			D48116P	A02		YC051-YC055
2201B	22	X2		KA	24-8	28-41-11	D40618P	A04			D48116P	A02		YC056-YR328
2201R	22	X2		KA	0-0	28-41-11	D40618P	A05			D48116P	B02		ALL
2201Z				KA	0-0	28-41-11	D40618P	PERG	1F		D48116P	PERG	1F	ALL
2601B	18	X2		SA	11-4	78-32-61	D40692P	5			TB0606V	B009	1	YC051-YC055
2601B	18	X2		SA	11-0	78-32-61	D40692P	5			TB0606V	B009	1	YC056-YL999, YN232-YR328
2601B	18	X2		SA	11-1	78-32-61	D40692P	5			TB0606V	B009	1	YN231
2601R	18	X2		SA	0-0	78-32-61	D40692P	6			TB0606V	A009	1	ALL
2601Z				SA	0-0	78-32-61	D40692P	S/R			GB00606	ST..	1A	ALL
2602B	18	X2		SB	11-4	78-32-61	D40692P	7			TB0606V	B011	1	YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5150

Page 27

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5158	286A5158				PSEU & AIR/GND SYS: M2061 & J24,J20 TO E/E BAY (ROUTE RIGHT) (continued)										
2602B	18	X2	SB		11-0	78-32-61	D40692P		7		TB0606V	B011	1		YC056-YL999, YN232-YR328
2602B	18	X2	SB		11-1	78-32-61	D40692P		7		TB0606V	B011	1		YN231
2602R	18	X2	SB		0-0	78-32-61	D40692P		8		TB0606V	A011	1		ALL
2602Z			SB		0-0	78-32-61	D40692P		S/R		GB00606	ST..	1A		ALL
2603B	24	Y2	SC		20-7	24-33-11	D40618P		A01		D40490J		1		YC051-YC055
2603B	24	Y2	SC		20-5	24-33-11	D40618P		A01		D40490J		1		YC056-YR328
2603R	24	Y2	SC		0-0	24-33-11	D40618P		B01		D40490J		3		ALL
2603Z			SC		0-0	24-33-11	D40618P		DED		D40490J	DED			ALL
2604B	24	Y2	SD		20-7	24-33-11	D40618P		A03		D40490J		15		YC051-YC055
2604B	24	Y2	SD		20-5	24-33-11	D40618P		A03		D40490J		15		YC056-YR328
2604R	24	Y2	SD		0-0	24-33-11	D40618P		B03		D40490J		16		ALL
2604Z			SD		0-0	24-33-11	D40618P		DED		D40490J	DED			ALL
2611B	24	Y2	SK		24-10	73-21-11	D40634P		1		D40484P	A01			YC051-YC055
2611B	24	Y2	SK		24-8	73-21-11	D40634P		1		D40484P	A01			YC056-YR328
2611R	24	Y2	SK		0-0	73-21-11	D40634P		2		D40484P	A02			ALL
2611Z			SK		0-0	73-21-11	D40634P			SK	D40484P	PERG	1F		ALL
5501	24	B6			14-6	21-51-11	D46120P		A10		D40640P		10		YC051-YC055
5501	24	B6			14-2	21-51-11	D46120P		A10		D40640P		10		YC056-YR328
5502	24	B6			28-6	21-51-11	D40640P		11		D40426P		10		YC051-YC055
5502	24	B6			28-10	21-51-11	D40640P		11		D40426P		10		YC056-YR328
6001	24	PK			29-3	73-23-11	D11140		3		D40486P	A03			YC051-YC055
6001	24	PK			29-7	73-23-11	D11140		3		D40486P	A03			YC056-YR328
6002	18	PA			11-4	78-32-61	D40692P		13		TB0606V	A015	1		YC051-YC055
6002	18	PA			11-0	78-32-61	D40692P		13		TB0606V	A015	1		YC056-YL999, YN232-YR328
6002	18	PA			11-1	78-32-61	D40692P		13		TB0606V	A015	1		YN231
6004	20	PA			14-0	78-34-21	D40702P		7		D40490J		9		YC051-YC055
6004	20	PA			13-11	78-34-21	D40702P		7		D40490J		9		YC056-YR328
6005	24	PK			24-6	73-22-31	D40702P		8		D40426P		12		YC051-YC055
6005	24	PK			24-10	73-22-31	D40702P		8		D40426P		12		YC056-YR328
6021	24	B6			13-7	76-21-21	D40634P		4		D40750P		13		ALL
6022	24	B6			14-3	76-21-21	D40634P		5		D46100P		19		YC051-YC055
6022	24	B6			13-11	76-21-21	D40634P		5		D46100P		19		YC056-YR328
6023	24	B6			14-3	76-21-21	D40634P		6		D46100P		20		YC051-YC055
6023	24	B6			13-11	76-21-21	D40634P		6		D46100P		20		YC056-YR328
FRGA					0-0	44-21-22	D40488P		11		D40488P			GA	YR314-YR328
FRS5					0-0	73-21-11	D40634P			SK	D40634P		3		ALL
FRS6					0-0	73-21-11	D40634P			SK	D40634P		S/R		ALL

WIRE LIST

D280A108

91-21-11

Section W5150

Page 28 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5160	286A5160				PSEU & AIR/GND SYS: M2061 & J4,J24 TO E/E BAY (ROUTE RIGHT)										
0001	16		PA		15-8	33-45-11	TB0040K	G001	1		TB0606V	B013	1		YC051-YD158
0002	16		PA		6-1	33-45-11	TB0040K	G002	1		GD00442	AC..	E	*	YC051-YD158, YL951-YR328
0003	22		PA		21-8	52-71-12	D10986		6		D40466P	20			YC051-YD158, YL951-YR328
0004	20		PA		33-1	52-71-13	D10986		20		D40292P	4			YC051-YC055
0004	20		PA		33-2	52-71-13	D10986		20		D40292P	4			YC056-YD158, YL951-YR328
0005	22		PA		14-4	52-71-12	D10986		37		D46122P	7			YC051-YD158, YL951-YR328
0006	18		PA		8-7	52-71-12	D10988		6	18	S00196	C	C		YC051-YD158, YL951-YR328
0007	20		CQ		33-1	52-71-13	D10986		8		D40292P	6			YC051-YC055
0007	20		CQ		33-2	52-71-13	D10986		8		D40292P	6			YC056-YD158, YL951-YR328
0008	20		PA		4-0	52-71-13	D10986		10		GD00034	DC..	1		YC051-YC055
0008	20		PA		4-2	52-71-13	D10986		10		GD00034	DC..	1		YC056-YD158, YL951-YR328
0009	20		PA		14-9	52-71-14	D10988		53		D46122P	16			YN231-YN501
0010	20		PA		14-4	52-71-14	D10986		47		D46122P	17			YN231-YN501
0011	20		PA		9-2	SPARE	D40610P		2		D46102P	24			YC051-YD158
0011	20		PA		9-2	33-45-11	D40610P		2		D46102P	24			YL951-YR328
0012	20		PA		9-2	SPARE	D40610P		9		D46102P	25			YC051-YD158
0012	20		PA		9-2	33-45-11	D40610P		9		D46102P	25			YL951-YR328
0013	18		PA		9-2	33-45-11	D46102P		23		D40610P	11			YL951-YL952, YN232-YN260
0013	18		PA		9-2	33-45-11	D40610P		11		D46102P	23			YL953-YN231, YN501-YR328
0014	16		PA		15-10	33-45-11	TB0040K	G001	1		D40610P	10			YL951-YN260, YR301-YR328
0014	16		PA		15-10	33-45-11	D40610P		10		TB0040K	G001	1		YN501
0017	20		PA		33-6	52-71-14	D10988		1		D40292P	8			YC051-YC055
0017	20		PA		33-7	52-71-14	D10988		1		D40292P	8			YC056-YD158, YL951-YR328
0018	20		PA		33-6	52-71-14	D10988		2		D40292P	12			YC051-YC055
0018	20		PA		33-7	52-71-14	D10988		2		D40292P	12			YC056-YD158, YL951-YR328
0019	20		PA		33-1	52-71-14	D10986		61		D40292P	11			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5160

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To					
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W5160	286A5160				PSEU & AIR/GND SYS: M2061 & J4,J24 TO E/E BAY (ROUTE RIGHT) (continued)											
0019	20		PA		33-2	52-71-14	D10986		61		D40292P		11		YC056-YD158, YL951-YR328	
0020	20		PA		14-9	52-71-14	D10988		31		D46122P		15		YN231-YN501	
0021	22		PA		14-4	52-71-11	D10986		60		D46122P		2		YC051-YD158, YL951-YR328	
0022	20		PA		33-6	52-71-13	D10988		21		D40292P		2		YC051-YC055	
0022	20		PA		33-7	52-71-13	D10988		21		D40292P		2		YC056-YD158, YL951-YR328	
0026	22		PA		14-4	52-71-12	D10986		33		D46122P		8		YC051-YD158, YL951-YR328	
0032	20		PA		4-0	25-51-21	D10986		32		GD00034	DC..	1		YC051-YC055	
0032	20		PA		4-2	25-51-21	D10986		32		GD00034	DC..	1		YC056-YD158, YL951-YL999, YR301-YR328	
0033	22		PA		14-9	52-71-12	D10988		33		D46122P		9		YC051-YD158, YL951-YR328	
0034	20		PA		14-4	52-71-13	D10986		40		D46122P		18		YC051-YD158, YL951-YR328	
0038	22		PA		16-1	SPARE	D10988		38		TB1808X	A003	1A		YC051-YD158, YL951-YR328	
0043	22		PA		14-4	52-71-11	D10986		59		D46122P		4		YC051-YD158, YL951-YR328	
0046	22		PA		24-5	52-71-12	D10986		56		D40472P	B02			YC051-YC055	
0046	22		PA		24-8	52-71-12	D10986		56		D40472P	B02			YC056-YD158, YL951-YR328	
0047	20		PA		14-5	33-36-12	D10986		55		D46102P		33		YC051-YD158, YL951-YR328	
0050	22		PA		14-9	52-71-11	D10988		20		D46122P		5		YC051-YD158, YL951-YR328	
0055	20		PA		14-10	33-36-11	D10988		55		D46102P		32		YC051-YD158, YL951-YR328	
0056	22		PA		24-10	52-71-12	D10988		56		D40472P	B01			YC051-YC055	
0056	22		PA		25-1	52-71-12	D10988		56		D40472P	B01			YC056-YD158, YL951-YR328	
0059	22		PA		14-9	52-71-11	D10988		59		D46122P		6		YC051-YD158, YL951-YR328	
0066	24		PK		22-1	21-31-23	D40464P		B08		D40472P	B08			YD158, YL951-YR328	
0067	24		PK		22-1	21-31-23	D40464P		B09		D40472P	B09			YD158, YL951-YR328	
0068	20		CQ		22-1	21-31-23	D40464P		B10		D40472P	B10			YD158, YL951-YR328	

WIRE LIST

D280A108

91-21-11

Section W5160

Page 2

Nov 12/2012



WIRE LIST
D280A108

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5160	286A5160				PSEU & AIR/GND SYS: M2061 & J4,J24 TO E/E BAY (ROUTE RIGHT) (continued)										
0305	22		PA		19-2	27-62-11	D40952P	B17			D43906P	4			YL953-YL999, YR301-YR328
0306	22		PA		19-2	27-62-11	D40952P	B18			D43906P	3			YL953-YL999, YR301-YR328
0501	22		PA		17-10	22-13-11	D40610P	13			D40464P	A01			YC051-YC055
0501	22		PA		18-0	22-13-11	D40610P	13			D40464P	A01			YC056-YD158, YL951-YR328
0502	22		PA		17-10	22-13-11	D40610P	12			D40464P	A02			YC051-YC055
0502	22		PA		18-0	22-13-11	D40610P	12			D40464P	A02			YC056-YD158, YL951-YR328
0505	18		HA		4-0	32-64-12	TB0044K	E001	1		GD00346	AC..	E		YC051-YC055
0505	18		HA		3-11	32-64-12	TB0044K	E001	1		GD00346	AC..	E		YC056-YD158, YL951-YR328
0506	22		PA		28-7	27-32-21	D10988	28			D40468P	B02			YC051-YC055
0506	22		PA		28-6	27-32-21	D10988	28			D40468P	B02			YC056-YD158, YL951-YR328
0508	20		PA		4-0	52-71-13	D10986	11			GD00034	DC..	1		YC051-YC055
0508	20		PA		4-2	52-71-13	D10986	11			GD00034	DC..	1		YC056-YD158, YL951-YL999, YR301-YR328
0509	20		PA		33-1	52-71-13	D40292P	3			D10986	52			YC051-YC055
0509	20		PA		33-2	52-71-13	D40292P	3			D10986	52			YC056-YD158, YL951-YL999, YR301-YR328
0510	20		PA		33-1	52-71-13	D40292P	5			D10986	53			YC051-YC055
0510	20		PA		33-2	52-71-13	D40292P	5			D10986	53			YC056-YD158, YL951-YL999, YR301-YR328
0511	22		PA		21-7	32-42-11	D40466P	1			D46102P	28			YC051-YD158, YL951-YR328
0512	22		PA		21-7	32-42-11	D40466P	2			D46102P	29			YC051-YD158, YL951-YR328
0513	20		PA		28-8	27-53-12	D40610P	3			D40468P	A02			YC051-YC055
0513	20		PA		28-7	27-53-12	D40610P	3			D40468P	A02			YC056-YD158, YL951-YR328
0514	20		PA		28-8	27-53-12	D40610P	4			D40468P	B01			YC051-YC055
0514	20		PA		28-7	27-53-12	D40610P	4			D40468P	B01			YC056-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11
Section W5160
Page 4
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5160	286A5160			PSEU & AIR/GND SYS: M2061 & J4,J24 TO E/E BAY (ROUTE RIGHT) (continued)											
0515	20		PA		12-7	27-53-12	TB1808X	A004	1A		D40610P	5			YC051-YD158, YL951-YR328
0516	20		PA		12-7	27-53-12	TB1808X	B004	1A		D40610P	14			YC051-YD158, YL951-YR328
0518	22		PA		11-4	29-23-11	D40694P		8		D10986	39			YC051-YC055
0518	22		PA		11-2	29-23-11	D40694P		8		D10986	39			YC056-YD158, YL951-YR328
0519	22		PA		2-8	29-23-11	SM00003			S	D10986	21			YC051-YD158, YL951-YR328
0520	22		PA		24-8	29-23-11	D40472P			B03	D10984	57			YC051-YC055
0520	22		PA		24-10	29-23-11	D40472P			B03	D10984	57			YC056-YD158, YL951-YR328
0522	22		PA		26-0	27-62-11	D40466P		40		D40474P	A01			YC051-YC055
0522	22		PA		25-10	27-62-11	D40466P		40		D40474P	A01			YC056-YD158, YL951-YR328
0523	22		PA		26-0	27-62-11	D40466P		41		D40474P	A02			YC051-YC055
0523	22		PA		25-10	27-62-11	D40466P		41		D40474P	A02			YC056-YD158, YL951-YR328
0524	22		PA		26-0	27-62-11	D40466P		42		D40474P	A03			YC051-YC055
0524	22		PA		25-10	27-62-11	D40466P		42		D40474P	A03			YC056-YD158, YL951-YR328
0525	22		PA		26-0	27-62-11	D40466P		43		D40474P	A04			YC051-YC055
0525	22		PA		25-10	27-62-11	D40466P		43		D40474P	A04			YC056-YD158, YL951-YR328
0526	22		PA		24-1	27-62-11	D46122P		26		D40474P	A05			YC051-YC055
0526	22		PA		24-0	27-62-11	D46122P		26		D40474P	A05			YC056-YD158, YL951-YR328
0527	20		PA		28-0	29-33-11	D46102P		1		D40468P	B09			YC051-YC055
0527	20		PA		27-11	29-33-11	D46102P		1		D40468P	B09			YC056-YD158, YL951-YR328
0528	22		PA		21-8	21-25-11	D40694P		15		D40474P	A08			YC051-YC055
0528	22		PA		21-5	21-25-11	D40694P		15		D40474P	A08			YC056-YD158, YL951-YR328
0529	22		PA		11-10	21-25-11	D40694P		14		D46102P	17			YC051-YC055
0529	22		PA		11-7	21-25-11	D40694P		14		D46102P	17			YC056-YD158, YL951-YR328
0530	22		PA		21-8	SPARE	D40694P		16		D40474P	B02			YC051-YC055
0530	22		PA		21-5	SPARE	D40694P		16		D40474P	B02			YC056-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5160

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To					
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W5160	286A5160				PSEU & AIR/GND SYS: M2061 & J4,J24 TO E/E BAY (ROUTE RIGHT) (continued)											
0531	22		PA		11-10	21-27-21	D40694P		17			D46102P	2			YC051-YC055
0531	22		PA		11-7	21-27-21	D40694P		17			D46102P	2			YC056-YD158, YL951-YR328
0532	22		PA		11-10	21-27-21	D40694P		18			D46102P	3			YC051-YC055
0532	22		PA		11-7	21-27-21	D40694P		18			D46102P	3			YC056-YD158, YL951-YR328
0533	20		PA		33-6	52-71-13	D40292P		1			D10988	35			YC051-YC055
0533	20		PA		33-7	52-71-13	D40292P		1			D10988	35			YC056-YD158, YL951-YL999, YR301-YR328
0535	20		PA		33-6	52-71-14	D10988		30			D40292P	7			YC051-YC055
0535	20		PA		33-7	52-71-14	D10988		30			D40292P	7			YC056-YD158, YL951-YL999, YR301-YR328
0536	20		PA		33-6	52-71-14	D10988		52			D40292P	9			YC051-YC055
0536	20		PA		33-7	52-71-14	D10988		52			D40292P	9			YC056-YD158, YL951-YL999, YR301-YR328
0537	22		PA		29-9	23-32-14	D40468P	A07				D40466P	18			YD158, YL951-YN260
0537	22		PA		29-9	44-21-22	D40468P	A07				D40466P	18			YN501-YR328
0538	22		PA		18-0	22-13-11	D40610P		8			D40464P	A10			YD157-YD158, YL951-YR328
0539	20		PA		33-1	52-71-14	D10986		15			D40292P	10			YC051-YC055
0539	20		PA		33-2	52-71-14	D10986		15			D40292P	10			YC056-YD158, YL951-YL999, YR301-YR328
0541	22		PA		14-8	32-64-12	D10984		7			D46102P	7			YC051-YD158, YL951-YR328
0542	22		PA		14-8	32-64-12	D10984		26			D46102P	8			YC051-YD158, YL951-YR328
0543	22		PA		14-8	32-64-12	D10984		32			D46102P	9			YC051-YD158, YL951-YR328
0544	22		PA		16-1	32-64-12	D10984		8			D40580P	4			YC051-YD158, YL951-YR328
0545	22		PA		16-1	32-64-12	D10984		25			D40580P	5			YC051-YD158, YL951-YR328
0546	22		PA		16-1	32-64-12	D10984		16			D40580P	6			YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5160

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY	Fam FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W5160	286A5160	PSEU & AIR/GND SYS: M2061 & J4,J24 TO E/E BAY (ROUTE RIGHT) (continued)			
0549	22 PA	14-8 32-64-21	D10984 52	D46102P 30	YC051-YD158, YL951-YR328
0550	20 PA	4-3 32-64-21	D10984 18	GD00034 DC.. 1	YC051-YC055
0550	20 PA	4-5 32-64-21	D10984 18	GD00034 DC.. 1	YC056-YD158, YL951-YR328
0553	20 PA	14-9 52-71-14	D10988 53	D46122P 16	YC051-YD158, YL951-YL999, YR301-YR328
0556	22 PA	14-8 32-64-21	D10984 53	D46102P 31	YC051-YD158, YL951-YR328
0557	22 PA	14-8 32-64-21	D10984 40	D46102P 14	YC051-YD158, YL951-YR328
0558	22 PA	14-8 32-64-21	D10984 41	D46102P 15	YC051-YD158, YL951-YR328
0559	22 PA	2-10 32-64-21	D10984 17	SM00002 S	YC051-YD158, YN231
0559	22 PA	21-11 32-64-21	D10984 17	D40466P 3	YL951-YL999, YN232-YR328
0560	22 PA	28-4 32-64-21	D10984 48	D40468P A01	YC051-YC055
0560	22 PA	28-3 32-64-21	D10984 48	D40468P A01	YC056-YD158, YL951-YR328
0561	22 PA	25-6 31-31-15	D40694P 1	D40470P B05	YC051-YC055
0561	22 PA	25-2 31-31-15	D40694P 1	D40470P B05	YC056-YD158, YL951-YR328
0562	22 PA	21-8 27-62-11	D40694P 26	D40474P A06	YC051-YC055
0562	22 PA	21-5 27-62-11	D40694P 26	D40474P A06	YC056-YD158, YL951-YR328
0563	22 PA	28-2 27-62-21	D10986 14	D40468P B06	YC051-YC055
0563	22 PA	28-1 27-62-21	D10986 14	D40468P B06	YC056-YD158, YL951-YR328
0564	22 PA	14-8 27-62-21	D10984 29	D46102P 26	YC051-YD158, YL951-YR328
0565	22 CQ	17-4 27-62-21	D10986 4	D40464P A09	YC051-YC055
0565	22 CQ	17-5 27-62-21	D10986 4	D40464P A09	YC056-YD158, YN231
0566	20 PA	14-4 52-71-14	D10986 47	D46122P 17	YC051-YD158, YL951-YL999, YR301-YR328
0567	22 PA	28-4 27-32-21	D10984 24	D40468P A03	YC051-YC055
0567	22 PA	28-3 27-32-21	D10984 24	D40468P A03	YC056-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5160

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W5160	286A5160				PSEU & AIR/GND SYS: M2061 & J4,J24 TO E/E BAY (ROUTE RIGHT) (continued)												
0568	22		PA		24-1	27-62-11	D46122P	29			D40474P	A07			YC051-YC055		
0568	22		PA		24-0	27-62-11	D46122P	29			D40474P	A07			YC056-YD158, YL951-YR328		
0569	20		PA		9-1	27-41-12	D40610P	7			D46122P	25			YC051-YD158, YL951-YR328		
0571	20		PA		14-7	52-71-14	D10984	54			D46122P	14			YC051-YD158, YL951-YL999, YR301-YR328		
0572	20		PA		14-9	52-71-14	D10988	31			D46122P	15			YC051-YD158, YL951-YL999, YR301-YR328		
0575	22		PA		14-10	32-64-21	D10988	8			D46102P	16			YC051-YD158, YL951-YR328		
0578	22		PA		14-8	31-53-11	D46102P	4			D10984	42			YC051-YD158, YL951-YR328		
0583	22		PA		28-4	31-53-11	D10984	51			D40470P	A03			YC051-YC055		
0583	22		PA		28-3	31-53-11	D10984	51			D40470P	A03			YC056-YD158, YL951-YR328		
0584	22		PA		27-11	31-31-15	D46122P	1			D40470P	B03			YC051-YC055		
0584	22		PA		27-10	31-31-15	D46122P	1			D40470P	B03			YC056-YD158, YL951-YR328		
0585	22		PA		11-6	21-27-21	D40694P	19			D46122P	38			YL951-YR328		
0586	22		PA		11-6	21-27-21	D40694P	28			D46122P	39			YL951-YR328		
0588	22		GK		11-9	34-41-11	D40694P	13			D46122P	13			YC051-YC052		
0588	22		GK		11-9	SPARE	D40694P	13			D46122P	13			YC053-YC055		
0588	22		GK		11-6	SPARE	D40694P	13			D46122P	13			YC056-YD158, YL951-YR328		
0589	22		PA		15-10	27-62-21	D10986	49			D40580P	1			YC051-YD158, YL951-YR328		
0590	22		PA		14-5	27-62-21	D10986	3			D46102P	27			YC051-YD158, YL951-YR328		
0593	22		PA		2-8	27-62-21	D10986	12			SM00002		S		YC051-YD158, YN231		
0594	22		PA		2-8	29-23-11	SM00003		S		D10986	9			YC051-YD158, YL951-YR328		
0595	22		PA		22-4	29-23-11	SM00003		S		D40472P	B04			YC051-YC055		
0595	22		PA		22-6	29-23-11	SM00003		S		D40472P	B04			YC056-YD158, YL951-YR328		
0596	20		PA		21-11	22-11-12	D10984	10			D40466P	38			YC051-YD158, YL951-YR328		

WIRE LIST

D280A108

91-21-11

Section W5160

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5160	286A5160				PSEU & AIR/GND SYS: M2061 & J4,J24 TO E/E BAY (ROUTE RIGHT) (continued)										
0597	22		PA		2-8	31-53-11	D10986	27			SM00004		S		YC051-YD158, YL951-YR328
0598	22		PA		2-8	31-53-11	D10986	48			SM00004		S		YC051-YD158, YL951-YR328
0599	22		PA		15-2	31-53-11	SM00004		S		D40464P	A03			YC051-YC055
0599	22		PA		15-4	31-53-11	SM00004		S		D40464P	A03			YC056-YD158, YL951-YR328
0602	22		PA		28-1	31-53-11	D10986	29			D40470P	B04			YC051-YC055
0602	22		PA		28-0	31-53-11	D10986	29			D40470P	B04			YC056-YD158, YL951-YR328
0603	18		PA		6-1	32-31-12	TB0040K	E003	1		GD00442	AC..	E	*	YC051-YD158, YL951-YR328
0609	22		PA		17-6	32-64-21	D10984	43			D40464P	A06			YC051-YC055
0609	22		PA		17-7	32-64-21	D10984	43			D40464P	A06			YC056-YD158, YL951-YR328
0610	22		PA		19-7	32-64-21	SM00002		S		D40466P	3			YC051-YD158, YN231
0611	22		PA		28-4	32-64-21	D10984	49			D40468P	B05			YC051-YC055
0611	22		PA		28-3	32-64-21	D10984	49			D40468P	B05			YC056-YD158, YL951-YR328
0612	22		CQ		28-7	49-52-31	D10988	51			D40468P	A09			YC051-YC055
0612	22		CQ		28-6	49-52-31	D10988	51			D40468P	A09			YC056-YD158, YL951-YR328
0614	22		PA		28-1	23-27-12	D10986	18			D40470P	A10			YC051-YC055
0614	22		PA		28-0	23-27-12	D10986	18			D40470P	A10			YC056-YD157
0614	22		PA		28-0	23-27-38	D10986	18			D40470P	A10			YD158, YL951-YR328
0615	22		PA		28-6	23-27-12	D10988	4			D40470P	B10			YC051-YC055
0615	22		PA		28-5	23-27-12	D10988	4			D40470P	B10			YC056-YD157
0615	22		PA		28-5	23-27-38	D10988	4			D40470P	B10			YD158, YL951-YR328
0616	22		PA		28-6	23-27-12	D10988	18			D40470P	B08			YC051-YC055
0616	22		PA		28-5	23-27-12	D10988	18			D40470P	B08			YC056-YD157
0616	22		PA		28-5	23-27-38	D10988	18			D40470P	B08			YD158, YL951-YR328
0617	22		PA		28-1	23-27-14	D10986	17			D40470P	A09			YC051-YC055
0617	22		PA		28-0	23-27-14	D10986	17			D40470P	A09			YC056-YD157
0617	22		PA		28-0	23-27-38	D10986	17			D40470P	A09			YD158, YL951-YR328
0618	22		PA		28-1	23-27-14	D10986	35			D40470P	B09			YC051-YC055
0618	22		PA		28-0	23-27-14	D10986	35			D40470P	B09			YC056-YD157
0618	22		PA		28-0	23-27-38	D10986	35			D40470P	B09			YD158, YL951-YR328
0619	22		PA		17-4	25-51-21	D10986	54			D40464P	B04			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5160

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5160	286A5160				PSEU & AIR/GND SYS: M2061 & J4,J24 TO E/E BAY (ROUTE RIGHT) (continued)										
0619	22		PA		17-5	25-51-21	D10986		54		D40464P		B04		YC056-YD158, YL951-YL999, YR301-YR328
0619	22		PA		17-5	SPARE	D10986		54		D40464P		B04		YN231-YN501
0620	20		PA		25-2	SPARE	D40694P		31		D40952P		A05		YL951-YR328
0622	20		PA		4-5	32-31-12	D10988		45		GD00034		DC..	1	YC051-YC055
0622	20		PA		4-7	32-31-12	D10988		45		GD00034		DC..	1	YC056-YD158, YL951-YR328
0623	22		PA		29-5	27-62-11	D40580P		2		D40470P		A07		YC051-YC055
0623	22		PA		29-4	27-62-11	D40580P		2		D40470P		A07		YC056-YD158, YL951-YR328
0624	22		PA		29-5	27-62-11	D40580P		3		D40470P		A08		YC051-YC055
0624	22		PA		29-4	27-62-11	D40580P		3		D40470P		A08		YC056-YD158, YL951-YR328
0625	22		PA		16-1	32-44-11	D40580P		7		D10984		28		YC051-YD158, YL951-YR328
0626	20		PA		14-8	23-34-01	D40694P		3		D40464P		A04		YC054-YC055
0626	20		PA		14-7	23-34-01	D40694P		3		D40464P		A04		YC056-YD158
0627	20		PA		14-8	23-34-01	D40694P		4		D40464P		A05		YC054-YC055
0627	20		PA		14-7	23-34-01	D40694P		4		D40464P		A05		YC056-YD157
0629	22		PA		14-10	SPARE	D10988		54		D46102P		20		YC051-YD158, YL951-YR328
0650	18		HA		8-11	32-64-12	TB0046K	E001	1		GD00446		AC..	E	YC051-YC055
0650	18		HA		8-10	32-64-12	TB0046K	E001	1		GD00446		AC..	E	YC056-YD158, YL951-YR328
0652	22		PA		21-7	23-34-01	D40466P		4		D46102P		18		YC051-YD158, YL951-YN260
0652	22		PA		21-7	44-21-26	D40466P		4		D46102P		18		YN501-YR328
0653	22		PA		21-7	23-34-01	D40466P		5		D46102P		19		YC051-YD158, YL951-YN260
0653	22		PA		21-7	44-21-26	D40466P		46		D46102P		21		YN501-YR328
0654	24		PK		21-6	23-31-06	D46122P		21		D40466P		10		YD158, YN231
0654	24		PK		21-6	23-31-06	D40466P		10		D46122P		21		YL951-YL999, YN232-YN260
0654	24		PK		21-6	44-21-22	D40466P		10		D46122P		21		YN501-YR328
0655	24		PK		21-6	23-31-06	D46122P		22		D40466P		11		YD158
0655	24		PK		21-6	23-31-06	D40466P		11		D46122P		22		YL951-YN260
0655	24		PK		21-6	44-21-22	D40466P		11		D46122P		22		YN501-YR328
0656	24		PK		29-9	SPARE	D40470P		A01		D40466P		27		YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5160

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W5160	286A5160				PSEU & AIR/GND SYS: M2061 & J4,J24 TO E/E BAY (ROUTE RIGHT) (continued)												
0656	24		PK		29-8	SPARE		D40470P	A01			D40466P	27			YC056-YD157, YL951-YR328	
0657	24		PK		29-9	SPARE		D40470P	A06			D40466P	28			YC051-YC055	
0657	24		PK		29-8	SPARE		D40470P	A06			D40466P	28			YC056-YD157, YL951-YR328	
0658	20		PA		29-8	SPARE		D40470P	B06			D40466P	16			YD158	
0658	20		PA		21-7	44-21-26		D40466P	16			D46102P	35			YN501-YR328	
0700	22		PA		19-4	32-42-11		D40466P	23			D11134	3			YC051-YC055	
0700	22		PA		19-5	32-42-11		D40466P	23			D11134	3			YC056-YD158, YL951-YR328	
0701	22		PA		20-6	32-42-11		D40466P	24			SP01502		S		YC051-YD158, YL951-YR328	
0702	22		PA		2-10	32-42-11		D11134	2			SP01502		S		YC051-YC055	
0702	22		PA		2-11	32-42-11		D11134	2			SP01502		S		YC056-YD158, YL951-YR328	
0703	22		PA		19-4	32-42-11		D40466P	25			D11134	6			YC051-YC055	
0703	22		PA		19-5	32-42-11		D40466P	25			D11134	6			YC056-YD158, YL951-YR328	
0704	22		PA		2-10	32-42-11		D11134	5			SP01504		S		YC051-YC055	
0704	22		PA		2-11	32-42-11		D11134	5			SP01504		S		YC056-YD158, YL951-YR328	
0705	22		PA		20-6	32-42-11		D40466P	26			SP01504		S		YC051-YD158, YL951-YR328	
1001R	22		X5	AA	19-1	SPARE		D40694P	21			D40466P	47			YC051-YC055	
1001R	22		X5	AA	18-11	SPARE		D40694P	21			D40466P	47			YC056-YD158, YL951-YR328	
1001Z				AA	0-0	SPARE		D40694P	DED			D40466P	DED			YC051-YD158, YL951-YR328	
1002R	22		X5	AB	19-1	SPARE		D40694P	22			D40466P	48			YC051-YC055	
1002R	22		X5	AB	18-11	SPARE		D40694P	22			D40466P	48			YC056-YD158, YL951-YR328	
1002Z				AB	0-0	SPARE		D40694P	DED			D40466P	DED			YC051-YD158, YL951-YR328	
1301	20		X1	EN	21-8	73-22-11		D40694P	11			D40474P	B01			YC051-YC055	
1301	20		X1	EN	21-5	73-22-11		D40694P	11			D40474P	B01			YC056-YD158, YL951-YR328	
1301Z				EN	0-0	73-22-11		D40694P			EN	D40474P	PERG	1F		YC051-YD158, YL951-YR328	
2003B	24		Y2	JC	25-5	27-32-22		D40952P	B07			D40464P	B07			YD158, YL951-YR328	

WIRE LIST

D280A108

91-21-11

Section W5160

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5160	286A5160				PSEU & AIR/GND SYS: M2061 & J4,J24 TO E/E BAY (ROUTE RIGHT) (continued)										
2003R	24	Y2	JC		0-0	27-32-22	D40952P	A07			D40464P	A07			YD158, YL951-YR328
2003Z			JC		0-0	27-32-22	D40952P	PERG	1F		D40464P	PERG	1F		YD158, YL951-YR328
2201B	22	PB	KA		24-10	24-22-21	D10988	47			D40472P	A01			YC051-YC055
2201B	22	PB	KA		25-1	24-22-21	D10988	47			D40472P	A01			YC056-YD158, YL951-YR328
2201R	22	PB	KA		0-0	24-22-21	D10988	48			D40472P	A02			YC051-YD158, YL951-YR328
2202B	22	PB	KB		31-7	27-62-37	D40468P	B10			D02537	1			YC051-YC055
2202B	22	PB	KB		31-3	27-62-37	D40468P	B10			D02537	1			YC056-YD158, YL951-YR328
2202R	22	PB	KB		0-0	27-62-37	D40468P	A10			D02537	2			YC051-YD158, YL951-YR328
2203B	22	PB	KC		24-1	24-22-21	D46122P	11			D40474P	A09			YC051-YC055
2203B	22	PB	KC		24-0	24-22-21	D46122P	11			D40474P	A09			YC056-YD158, YL951-YR328
2203R	22	PB	KC		0-0	24-22-21	D46122P	12			D40474P	A10			YC051-YD158, YL951-YR328
2205B	20	HB	KE		12-8	32-64-12	D10984	19			TB0046K	C001	1		YC051-YC055
2205B	20	HB	KE		12-7	32-64-12	D10984	19			TB0046K	C001	1		YC056-YD158, YL951-YR328
2205R	20	HB	KE		0-0	32-64-12	D10984	20			TB0046K	A001	1		YC051-YD158, YL951-YR328
2206B	20	HB	KF		12-5	32-64-12	D10984	2			SM00007		S		YC051-YD158, YL951-YR328
2206R	20	HB	KF		0-0	32-64-12	D10984	9			SM00006		S		YC051-YD158, YL951-YR328
2210B	24	Y2	KJ		19-1	23-27-39	D43906P	23			D40952P	A19			YL951-YL952, YN232-YN235
2210B	24	Y2	KJ		19-2	23-27-39	D43906P	23			D40952P	A19			YL953-YL954, YN231
2210R	24	Y2	KJ		0-0	23-27-39	D43906P	24			D40952P	A20			YL951-YL954, YN231-YN235
2210Z			KJ		0-0	23-27-39	D43906P	22			D40952P	PERG	1F		YL951-YL954, YN231-YN235
2211B	24	Y2	KK		19-1	23-27-39	D43906P	27			D40952P	A18			YL951-YL952, YN232-YN235
2211B	24	Y2	KK		19-2	23-27-39	D43906P	27			D40952P	A18			YL953-YL954, YN231
2211R	24	Y2	KK		0-0	23-27-39	D43906P	26			D40952P	A17			YL951-YL954, YN231-YN235

WIRE LIST
D280A108

91-21-11
Section W5160
Page 12
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5160	286A5160			PSEU & AIR/GND SYS: M2061 & J4,J24 TO E/E BAY (ROUTE RIGHT) (continued)											
2211Z				KK	0-0	23-27-39	D43906P	25			D40952P	PERG	1F		YL951-YL954, YN231-YN235
2212B	24	Y2	KL		19-1	23-27-39	D43906P	30			D40952P	A16			YL951-YL952, YN232-YN235
2212B	24	Y2	KL		19-2	23-27-39	D43906P	30			D40952P	A16			YL953-YL954, YN231
2212R	24	Y2	KL		0-0	23-27-39	D43906P	29			D40952P	A15			YL951-YL954, YN231-YN235
2212Z				KL	0-0	23-27-39	D43906P	28			D40952P	PERG	1F		YL951-YL954, YN231-YN235
2213B	18	HM	KM		3-7	32-64-12	TB0044K	C001	1		SM00007		S		YC051-YD158, YL951-YR328
2213R	18	HM	KM		0-0	32-64-12	TB0044K	A001	1		SM00006		S		YC051-YD158, YL951-YR328
2221B	22	PB	KV		21-11	32-64-12	D10984	55			D40466P	8			YC051-YD158, YL951-YR328
2221R	22	PB	KV		0-0	32-64-12	D10984	33			D40466P	9			YC051-YD158, YL951-YR328
2222B	22	PB	KW		21-11	32-64-12	D10984	15			D40466P	6			YC051-YD158, YL951-YR328
2222R	22	PB	KW		0-0	32-64-12	D10984	5			D40466P	7			YC051-YD158, YL951-YR328
2223B	22	PB	KX		14-8	32-64-12	D10984	12			D46102P	10			YC051-YD158, YL951-YR328
2223R	22	PB	KX		0-0	32-64-12	D10984	11			D46102P	11			YC051-YD158, YL951-YR328
2224B	22	PB	KY		14-8	32-64-12	D10984	46			D46102P	12			YC051-YD158, YL951-YR328
2224R	22	PB	KY		0-0	32-64-12	D10984	45			D46102P	13			YC051-YD158, YL951-YR328
2227B	20	HB	LB		19-4	32-31-12	D10988	23			TB0040K	C003	1		YC051-YD158, YL951-YR328
2227R	20	HB	LB		0-0	32-31-12	D10988	42			TB0040K	A003	1		YC051-YD158, YL951-YR328
2232B	24	PL	LG		14-10	32-31-12	D10988	10			D46102P	5			YC051-YD158, YL951-YR328
2232R	24	PL	LG		0-0	32-31-12	D10988	24			D46102P	6			YC051-YD158, YL951-YR328
2233B	24	PL	LH		22-1	32-31-12	D10988	40			D40466P	14			YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5160

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5160	286A5160				PSEU & AIR/GND SYS: M2061 & J4,J24 TO E/E BAY (ROUTE RIGHT) (continued)										
2233R	24	PL	LH		0-0	32-31-12	D10988		41		D40466P		15		YC051-YD158, YL951-YR328
2409B	22	PB	OI		24-5	52-71-11	D10986		36		D40472P		A04		YC051-YC055
2409B	22	PB	OI		24-8	52-71-11	D10986		36		D40472P		A04		YC056-YD158, YL951-YR328
2409R	22	PB	OI		0-0	52-71-11	D10986		19		D40472P		A03		YC051-YD158, YL951-YR328
2419B	22	PB	OT		24-10	52-71-11	D10988		36		D40472P		A10		YC051-YC055
2419B	22	PB	OT		25-1	52-71-11	D10988		36		D40472P		A10		YC056-YD158, YL951-YR328
2419R	22	PB	OT		0-0	52-71-11	D10988		19		D40472P		A09		YC051-YD158, YL951-YR328
2444B	22	PB	PT		24-5	52-71-11	D10986		57		D40472P		A08		YC051-YC055
2444B	22	PB	PT		24-8	52-71-11	D10986		57		D40472P		A08		YC056-YD158, YL951-YR328
2444R	22	PB	PT		0-0	52-71-11	D10986		58		D40472P		A07		YC051-YD158, YL951-YR328
2458B	22	PB	QH		24-10	52-71-11	D10988		57		D40472P		A06		YC051-YC055
2458B	22	PB	QH		25-1	52-71-11	D10988		57		D40472P		A06		YC056-YD158, YL951-YR328
2458R	22	PB	QH		0-0	52-71-11	D10988		58		D40472P		A05		YC051-YD158, YL951-YR328
2460B	22	PB	QJ		24-10	SPARE	D10988		60		D40472P		B06		YC051-YC055
2460B	22	PB	QJ		25-1	SPARE	D10988		60		D40472P		B06		YC056-YD158, YL951-YR328
2460R	22	PB	QJ		0-0	SPARE	D10988		61		D40472P		B05		YC051-YD158, YL951-YR328
2461B	24	Y2	QK		29-9	SPARE	D40470P		B07		D40466P		30		YC051-YC055
2461B	24	Y2	QK		29-8	SPARE	D40470P		B07		D40466P		30		YC056-YD157, YL951-YL952, YN231-YR328
2461R	24	Y2	QK		0-0	SPARE	D40470P		B06		D40466P		29		YC051-YD157, YL951-YL952, YN231-YR328
2461Z			QK		0-0	SPARE	D40470P	PERG	1F		D40466P		31		YC051-YD157, YL951-YL952, YN231-YR328
3202B	22	PC	YB		31-7	27-62-37	D40468P		B08		D02537		5		YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5160

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5160	286A5160			PSEU & AIR/GND SYS: M2061 & J4,J24 TO E/E BAY (ROUTE RIGHT) (continued)											
3202B	22	PC	YB		31-3	27-62-37	D40468P	B08			D02537	5			YC056-YD158, YL951-YR328
3202R	22	PC	YB		0-0	27-62-37	D40468P	A08			D02537	4			YC051-YD158, YL951-YR328
3202Y	22	PC	YB		0-0	27-62-37	D40468P	B07			D02537	3			YC051-YD158, YL951-YR328
5501	24	PK			28-7	21-51-24	D40468P	A04			D10988	27			YC051-YC055
5501	24	PK			28-6	21-51-24	D40468P	A04			D10988	27			YC056-YD158, YL951-YR328
5503	24	PK			28-7	21-31-24	D40468P	A05			D10988	12			YC051-YC055
5503	24	PK			28-6	21-31-24	D40468P	A05			D10988	12			YC056-YD158, YL951-YR328
6002	24	PK			25-6	73-22-11	D40694P	9			D40470P	A04			YC051-YC055
6002	24	PK			25-2	73-22-11	D40694P	9			D40470P	A04			YC056-YD158, YL951-YR328
6004	24	PK			28-7	73-23-11	D10988	26			D40468P	A06			YC051-YC055
6004	24	PK			28-6	73-23-11	D10988	26			D40468P	A06			YC056-YD158, YL951-YR328
6005	24	PK			25-6	76-21-21	D40694P	7			D40470P	A05			YC051-YC055
6005	24	PK			25-2	76-21-21	D40694P	7			D40470P	A05			YC056-YD158, YL951-YR328
6006	20	PA			27-11	28-42-11	D40470P	A02			D46122P	27			YC051-YC055
6006	20	PA			27-10	28-42-11	D40470P	A02			D46122P	27			YC056-YD158, YL951-YR328
6007	20	PA			27-11	28-42-11	D40470P	B02			D46122P	28			YC051-YC055
6007	20	PA			27-10	28-42-11	D40470P	B02			D46122P	28			YC056-YD158, YL951-YR328
6008	24	PK			25-6	73-22-31	D40470P	B01			D40694P	12			YC051-YC055
6008	24	PK			25-2	73-22-31	D40470P	B01			D40694P	12			YC056-YD158, YL951-YR328
6021	20	PA			25-8	78-34-21	D40952P	B01			D11134	9			YC051-YC055
6021	20	PA			25-9	78-34-21	D40952P	B01			D11134	9			YC056-YD158, YL951-YR328
6022	20	PA			25-8	78-34-21	D40952P	B02			D11134	15			YC051-YC055
6022	20	PA			25-9	78-34-21	D40952P	B02			D11134	15			YC056-YD158, YL951-YR328
6023	20	PA			2-10	78-34-21	D11134	14			SP00968		S		YC051-YC055
6023	20	PA			2-11	78-34-21	D11134	14			SP00968		S		YC056-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5160

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5160	286A5160				PSEU & AIR/GND SYS: M2061 & J4,J24 TO E/E BAY (ROUTE RIGHT) (continued)										
6024	20		PA		25-8	78-34-21	D40952P	B04			D11134	8			YC051-YC055
6024	20		PA		25-9	78-34-21	D40952P	B04			D11134	8			YC056-YD158, YL951-YR328
6025	20		PA		9-7	78-34-21	D40694P	27			D11134	7			YC051-YC055
6025	20		PA		9-6	78-34-21	D40694P	27			D11134	7			YC056-YD158, YL951-YR328
6026	20		PA		26-10	78-34-21	D40952P	B03			SP00968		S		YC051-YC055
6026	20		PA		26-9	78-34-21	D40952P	B03			SP00968		S		YC056-YD158, YL951-YR328
6027	20		PA		25-6	78-34-21	D40952P	B05			D40694P	30			YC051-YC055
6027	20		PA		25-2	78-34-21	D40952P	B05			D40694P	30			YC056-YD158, YL951-YR328
6028	20		PA		25-6	78-34-21	D40952P	B06			D40694P	29			YC051-YC055
6028	20		PA		25-2	78-34-21	D40952P	B06			D40694P	29			YC056-YD158, YL951-YR328
FRE1					0-0	73-22-11	D40694P			EN	D40694P	23			YC051-YD158, YL951-YR328
FRE2					0-0	73-22-11	D40694P			EN	D40694P	S/R			YC051-YD158, YL951-YR328
W5161	286A5161				E1-1, E3-1, E5-2										
0001	22		CQ		13-10	22-13-11	D41155P	A16			D45255J	A16			ALL
0003	22		PA		13-10	34-61-12	D41155P	B01			D45255J	B11			ALL
0004	20		PA		32-1	SPARE	D43145P	A05			D45245J	B15			YC051-YC055
0004	20		PA		32-4	SPARE	D43145P	A05			D45245J	B15			YC056-YR328
0005	22		PA		32-0	34-61-12	D43155P	A17			D45255J	B13			YC051-YC055
0005	22		PA		32-3	34-61-12	D43155P	A17			D45255J	B13			YC056-YR328
0006	22		PA		32-0	34-61-12	D43155P	A18			D45255J	B14			YC051-YC055
0006	22		PA		32-3	34-61-12	D43155P	A18			D45255J	B14			YC056-YR328
0009	24		PK		32-1	31-62-15	D43145P	B13			D45245J	A10			YC051-YC055
0009	24		PK		32-4	31-62-15	D43145P	B13			D45245J	A10			YC056-YR328
0010	22		PA		13-9	34-61-16	D41155P	B04			D45245J	A07			ALL
0011	22		PA		13-9	34-61-16	D41155P	B05			D45245J	A08			ALL
0012	22		PA		13-10	34-16-11	D41155P	A11			D45255J	A07			ALL
0014	22		PA		0-7	34-21-12	D03691	17			D03691	14			ALL
0015	22		PA		0-7	34-21-12	D03691	20			D03691	13			ALL
0016	22		PA		0-7	34-21-12	D03691	9			D03691	12			ALL
0017	20		PA		4-7	34-21-12	D03691	18			GD00420	DC..	1A		YC051-YC055
0017	20		PA		4-4	34-21-12	D03691	18			GD00420	DC..	1A		YC056-YR328

WIRE LIST

D280A108

91-21-11
Section W5160
Page 16
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From			To			Effectivity		
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W5161	286A5161				E1-1, E3-1, E5-2 (continued)										
0018	22		CQ		13-9	22-18-11	D45245J	B03			D41155P	B12			ALL
0019	22		PA		13-9	23-43-11	D45245J	B07			D41155P	B13			ALL
0020	22		PA		13-9	SPARE	D45245J	B08			D41155P	B14			YC051-YD157
0020	22		PA		13-9	23-42-11	D45245J	B08			D41155P	B14			YD158-YR328
0021	22		PA		13-9	SPARE	D45245J	B09			D41155P	B11			YC051-YC058
0022	24		PK		32-0	31-62-15	D43155P	A01			D45245J	B10			YC051-YC055
0022	24		PK		32-2	31-62-15	D43155P	A01			D45245J	B10			YC056-YR328
0023	24		PK		32-0	31-62-15	D43155P	A02			D45245J	B11			YC051-YC055
0023	24		PK		32-2	31-62-15	D43155P	A02			D45245J	B11			YC056-YR328
0024	24		PK		32-0	31-62-15	D43155P	A03			D45245J	B12			YC051-YC055
0024	24		PK		32-2	31-62-15	D43155P	A03			D45245J	B12			YC056-YR328
0025	22		PA		13-9	34-61-17	D45245J	A20			D41155P	B20			ALL
0026	22		PA		14-0	34-21-11	D41145P	A01			D45245J	B04			ALL
0027	20		PA		32-1	SPARE	D43145P	A03			D45245J	B13			YC051-YC055
0027	20		PA		32-4	SPARE	D43145P	A03			D45245J	B13			YC056-YR328
0028	20		PA		32-1	SPARE	D43145P	A04			D45245J	B14			YC051-YC055
0028	20		PA		32-4	SPARE	D43145P	A04			D45245J	B14			YC056-YR328
0029	24		PK		32-2	73-21-31	D45265J	A01			D43145P	A06			YC051-YC055
0029	24		PK		32-4	73-21-31	D45265J	A01			D43145P	A06			YC056-YR328
0030	24		PK		32-2	73-21-31	D45265J	A02			D43145P	A07			YC051-YC055
0030	24		PK		32-4	73-21-31	D45265J	A02			D43145P	A07			YC056-YR328
0031	24		PK		32-2	73-21-31	D45265J	A03			D43145P	A08			YC051-YC055
0031	24		PK		32-4	73-21-31	D45265J	A03			D43145P	A08			YC056-YR328
0032	24		PK		32-2	73-21-31	D45265J	A04			D43145P	A09			YC051-YC055
0032	24		PK		32-4	73-21-31	D45265J	A04			D43145P	A09			YC056-YR328
0033	24		PK		32-2	73-21-31	D45265J	A05			D43145P	A10			YC051-YC055
0033	24		PK		32-4	73-21-31	D45265J	A05			D43145P	A10			YC056-YR328
0034	24		PK		32-0	31-62-15	D43155P	A04			D45245J	B16			YC051-YC055
0034	24		PK		32-2	31-62-15	D43155P	A04			D45245J	B16			YC056-YR328
0035	24		PK		22-5	SPARE	D41145P	A04			D43145P	B01			YC051-YC055
0035	24		PK		22-8	SPARE	D41145P	A04			D43145P	B01			YC056-YR328
0038	22		PA		14-0	34-21-11	D41145P	A05			D45245J	B05			ALL
0039	20		PA		13-10	34-61-22	D45255J	B07			D41155P	B10			ALL
0040	24		PK		22-2	SPARE	D43145P	A17			D41155P	A17			YC051-YC055
0040	24		PK		22-5	SPARE	D43145P	A17			D41155P	A17			YC056-YR328
0041	20		PA		13-10	34-61-22	D45255J	B08			D41155P	B09			ALL
0042	22		PA		13-9	SPARE	D45245J	B06			D41155P	B17			YC051-YD157
2501B	24		Y2	AA	13-10	34-21-14	D45255J	A02			D41155P	A02			ALL
2501R	24		Y2	AA	0-0	34-21-14	D45255J	A01			D41155P	A01			ALL

WIRE LIST

D280A108

91-21-11

Section W5160

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5161	286A5161				E1-1, E3-1, E5-2 (continued)										
2501Z				AA	0-0	34-21-14	D45255J	PERG	1F		D41155P	PERG	1F		ALL
2502B	24	Y2		AB	13-10	34-21-14	D45255J	A04			D41155P	A04			ALL
2502R	24	Y2		AB	0-0	34-21-14	D45255J	A03			D41155P	A03			ALL
2502Z				AB	0-0	34-21-14	D45255J	PERG	1F		D41155P	PERG	1F		ALL
2503B	24	Y2		AC	13-10	34-21-14	D45255J	A06			D41155P	A06			YC051-YD155
2503B	24	Y2		AC	13-10	SPARE	D45255J	A06			D41155P	A06			YD157-YR328
2503R	24	Y2		AC	0-0	34-21-14	D45255J	A05			D41155P	A05			YC051-YD155
2503R	24	Y2		AC	0-0	SPARE	D45255J	A05			D41155P	A05			YD157-YR328
2503Z				AC	0-0	34-21-14	D45255J	PERG	1F		D41155P	PERG	1F		YC051-YD155
2503Z				AC	0-0	SPARE	D45255J	PERG	1F		D41155P	PERG	1F		YD157-YR328
2505B	24	Y2		AE	13-10	22-31-52	D45255J	B04			D41155P	A10			ALL
2505R	24	Y2		AE	0-0	22-31-52	D45255J	B03			D41155P	A09			ALL
2505Z				AE	0-0	22-31-52	D45255J	PERG	1F		D41155P	PERG	1F		ALL
2506B	24	Y2		AF	32-0	34-21-13	D43155P	A06			D45255J	A09			YC051-YC055
2506B	24	Y2		AF	32-3	34-21-13	D43155P	A06			D45255J	A09			YC056-YR328
2506R	24	Y2		AF	0-0	34-21-13	D43155P	A05			D45255J	A08			ALL
2506Z				AF	0-0	34-21-13	D43155P	PERG	1F		D45255J	PERG	1F		ALL
2507B	24	Y2		AG	32-0	34-21-13	D43155P	A08			D45255J	A11			YC051-YC055
2507B	24	Y2		AG	32-3	34-21-13	D43155P	A08			D45255J	A11			YC056-YR328
2507R	24	Y2		AG	0-0	34-21-13	D43155P	A07			D45255J	A10			ALL
2507Z				AG	0-0	34-21-13	D43155P	PERG	1F		D45255J	PERG	1F		ALL
2508B	24	Y2		AH	13-10	34-21-13	D41155P	A13			D45255J	A13			ALL
2508R	24	Y2		AH	0-0	34-21-13	D41155P	A12			D45255J	A12			ALL
2508Z				AH	0-0	34-21-13	D41155P	PERG	1F		D45255J	PERG	1F		ALL
2509B	24	Y2		AI	13-10	34-21-13	D41155P	A15			D45255J	A15			ALL
2509R	24	Y2		AI	0-0	34-21-13	D41155P	A14			D45255J	A14			ALL
2509Z				AI	0-0	34-21-13	D41155P	PERG	1F		D45255J	PERG	1F		ALL
2510B	24	M5		AJ	22-2	34-49-11	D41155P	A19			D43145P	A19			YC051-YC055
2510B	24	M5		AJ	22-5	34-49-11	D41155P	A19			D43145P	A19			YC056-YR328
2510R	24	M5		AJ	0-0	34-49-11	D41155P	A18			D43145P	A18			ALL
2510ZI				AJ	0-0	34-49-11	D41155P	A20			D43145P	A20			ALL
2510ZO				AJ	0-0	34-49-11	D41155P	PERG	1F		D43145P	PERG	1F		ALL
2511B	22	X2		AK	22-4	SPARE	D41145P	A03			D43155P	B16			YC051-YC055
2511B	22	X2		AK	22-7	SPARE	D41145P	A03			D43155P	B16			YC056-YR328
2511R	22	X2		AK	0-0	SPARE	D41145P	A02			D43155P	B15			ALL
2511Z				AK	0-0	SPARE	D41145P	PERG	1F		D43155P	PERG	1F		ALL
2513B	24	Y2		AM	32-0	31-62-15	D43155P	A12			D45245J	B18			YC051-YC055
2513B	24	Y2		AM	32-2	31-62-15	D43155P	A12			D45245J	B18			YC056-YR328
2513R	24	Y2		AM	0-0	31-62-15	D43155P	A11			D45245J	B17			ALL

WIRE LIST

D280A108

91-21-11

Section W5160

Page 18

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5161		286A5161			E1-1, E3-1, E5-2 (continued)										
	2513Z			AM	0-0	31-62-15	D43155P	PERG	1F		D45245J	PERG	1F		ALL
	2514B	24	Y2	AN	32-0	31-62-15	D43155P	A14			D45245J	B20			YC051-YC055
	2514B	24	Y2	AN	32-2	31-62-15	D43155P	A14			D45245J	B20			YC056-YR328
	2514R	24	Y2	AN	0-0	31-62-15	D43155P	A13			D45245J	B19			ALL
	2514Z			AN	0-0	31-62-15	D43155P	PERG	1F		D45245J	PERG	1F		ALL
	2516B	24	Y2	AQ	13-10	34-61-14	D41155P	B03			D45255J	B16			ALL
	2516R	24	Y2	AQ	0-0	34-61-14	D41155P	B02			D45255J	B15			ALL
	2516Z			AQ	0-0	34-61-14	D41155P	PERG	1F		D45255J	PERG	1F		ALL
	2517B	24	Y2	AR	32-0	34-61-14	D43155P	A20			D45255J	B18			YC051-YC055
	2517B	24	Y2	AR	32-3	34-61-14	D43155P	A20			D45255J	B18			YC056-YR328
	2517R	24	Y2	AR	0-0	34-61-14	D43155P	A19			D45255J	B17			ALL
	2517Z			AR	0-0	34-61-14	D43155P	PERG	1F		D45255J	PERG	1F		ALL
	2518B	24	Y2	AS	32-0	SPARE	D43155P	B02			D45255J	B20			YC051-YC055
	2518B	24	Y2	AS	32-3	SPARE	D43155P	B02			D45255J	B20			YC056-YR328
	2518R	24	Y2	AS	0-0	SPARE	D43155P	B01			D45255J	B19			ALL
	2518Z			AS	0-0	SPARE	D43155P	PERG	1F		D45255J	PERG	1F		ALL
	2519B	22	X2	AT	13-9	34-61-15	D41155P	B19			D45245J	A02			ALL
	2519R	22	X2	AT	0-0	34-61-15	D41155P	B18			D45245J	A01			ALL
	2519Z			AT	0-0	34-61-15	D41155P	PERG	1F		D45245J	PERG	1F		ALL
	2520B	22	X2	AU	32-0	34-61-15	D43155P	B04			D45245J	A04			YC051-YC055
	2520B	22	X2	AU	32-2	34-61-15	D43155P	B04			D45245J	A04			YC056-YR328
	2520R	22	X2	AU	0-0	34-61-15	D43155P	B03			D45245J	A03			ALL
	2520Z			AU	0-0	34-61-15	D43155P	PERG	1F		D45245J	PERG	1F		ALL
	2521B	22	X2	AV	32-0	34-61-15	D43155P	B06			D45245J	A06			YC051-YC055
	2521B	22	X2	AV	32-2	34-61-15	D43155P	B06			D45245J	A06			YC056-YR328
	2521R	22	X2	AV	0-0	34-61-15	D43155P	B05			D45245J	A05			ALL
	2521Z			AV	0-0	34-61-15	D43155P	PERG	1F		D45245J	PERG	1F		ALL
	2522B	22	X2	AW	32-0	34-61-18	D43155P	B08			D45255J	A18			YC051-YC055
	2522B	22	X2	AW	32-3	34-61-18	D43155P	B08			D45255J	A18			YC056-YC058
	2522B	22	X2	AW	13-10	31-32-15	D41155P	B11			D45255J	A18			YC059-YR328
	2522R	22	X2	AW	0-0	34-61-18	D43155P	B07			D45255J	A17			YC051-YC058
	2522R	22	X2	AW	0-0	31-32-15	D41155P	B06			D45255J	A17			YC059-YR328
	2522Z			AW	0-0	34-61-18	D43155P	PERG	1F		D45255J	PERG	1F		YC051-YC058
	2522Z			AW	0-0	31-32-15	D41155P	PERG	1F		D45255J	PERG	1F		YC059-YR328
	2523B	24	Y2	AX	32-0	SPARE	D45265J	B02			D43155P	B10			YC051-YC055
	2523B	24	Y2	AX	32-3	SPARE	D45265J	B02			D43155P	B10			YC056-YR328
	2523R	24	Y2	AX	0-0	SPARE	D45265J	B01			D43155P	B09			ALL
	2523Z			AX	0-0	SPARE	D45265J	PERG	1F		D43155P	PERG	1F		ALL
	2524B	24	Y2	AY	32-1	31-62-15	D43145P	B12			D45245J	A12			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5160

Page 19

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5161	286A5161				E1-1, E3-1, E5-2 (continued)										
2524B	24	Y2	AY		32-4	31-62-15	D43145P	B12			D45245J	A12			YC056-YR328
2524R	24	Y2	AY		0-0	31-62-15	D43145P	B11			D45245J	A11			ALL
2524Z			AY		0-0	31-62-15	D43145P	PERG	1F		D45245J	PERG	1F		ALL
2525B	24	Y2	AZ		32-1	31-62-15	D43145P	B15			D45245J	A14			YC051-YC055
2525B	24	Y2	AZ		32-4	31-62-15	D43145P	B15			D45245J	A14			YC056-YR328
2525R	24	Y2	AZ		0-0	31-62-15	D43145P	B14			D45245J	A13			ALL
2525Z			AZ		0-0	31-62-15	D43145P	PERG	1F		D45245J	PERG	1F		ALL
2526B	24	Y2	BA		32-1	31-62-15	D43145P	B17			D45245J	A16			YC051-YC055
2526B	24	Y2	BA		32-4	31-62-15	D43145P	B17			D45245J	A16			YC056-YR328
2526R	24	Y2	BA		0-0	31-62-15	D43145P	B16			D45245J	A15			ALL
2526Z			BA		0-0	31-62-15	D43145P	PERG	1F		D45245J	PERG	1F		ALL
2527B	24	Y2	BB		30-10	34-21-12	D03691	8			D45245J	B02			YC051-YC055
2527B	24	Y2	BB		30-11	34-21-12	D03691	8			D45245J	B02			YC056-YR328
2527R	24	Y2	BB		0-0	34-21-12	D03691	7			D45245J	B01			ALL
2527Z			BB		0-0	34-21-12	D03691	PERB			D45245J	PERG	1F		ALL
2529B	24	Y2	BD		32-2	34-21-14	D43145P	A12			D45265J	A07			YC051-YC055
2529B	24	Y2	BD		32-4	34-21-14	D43145P	A12			D45265J	A07			YC056-YR328
2529R	24	Y2	BD		0-0	34-21-14	D43145P	A11			D45265J	A06			ALL
2529Z			BD		0-0	34-21-14	D43145P	PERG	1F		D45265J	PERG	1F		ALL
2530B	24	Y2	BE		32-2	34-21-14	D43145P	A14			D45265J	A09			YC051-YC055
2530B	24	Y2	BE		32-4	34-21-14	D43145P	A14			D45265J	A09			YC056-YR328
2530R	24	Y2	BE		0-0	34-21-14	D43145P	A13			D45265J	A08			ALL
2530Z			BE		0-0	34-21-14	D43145P	PERG	1F		D45265J	PERG	1F		ALL
2531B	22	X2	BF		22-4	SPARE	D41145P	B02			D43155P	B12			YC051-YC055
2531B	22	X2	BF		22-7	SPARE	D41145P	B02			D43155P	B12			YC056-YC058
2531B	22	X2	BF		22-7	31-32-15	D41145P	B02			D43155P	B08			YC059-YR328
2531R	22	X2	BF		0-0	SPARE	D41145P	B01			D43155P	B11			YC051-YC058
2531R	22	X2	BF		0-0	31-32-15	D41145P	B01			D43155P	B07			YC059-YR328
2531Z			BF		0-0	SPARE	D41145P	PERG	1F		D43155P	PERG	1F		YC051-YC058
2531Z			BF		0-0	31-32-15	D41145P	PERG	1F		D43155P	PERG	1F		YC059-YR328
2532B	24	Y2	BG		22-5	22-11-51	D41145P	B04			D43145P	B04			YC051-YC055
2532B	24	Y2	BG		22-8	22-11-51	D41145P	B04			D43145P	B04			YC056-YR328
2532R	24	Y2	BG		0-0	22-11-51	D41145P	B03			D43145P	B03			ALL
2532Z			BG		0-0	22-11-51	D41145P	PERG	1F		D43145P	PERG	1F		ALL
2533B	24	Y2	BH		22-5	34-33-11	D41145P	A08			D43145P	A02			YC051-YC055
2533B	24	Y2	BH		22-8	34-33-11	D41145P	A08			D43145P	A02			YC056-YR328
2533R	24	Y2	BH		0-0	34-33-11	D41145P	A07			D43145P	A01			ALL
2533Z			BH		0-0	34-33-11	D41145P	PERG	1F		D43145P	PERG	1F		ALL
2534B	24	Y2	BI		22-5	34-33-11	D41145P	A10			D43145P	A16			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5160

Page 20

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5161		286A5161				E1-1, E3-1, E5-2 (continued)										
2534B		24		Y2	BI	22-8	34-33-11	D41145P	A10			D43145P	A16			YC056-YR328
2534R		24		Y2	BI	0-0	34-33-11	D41145P	A09			D43145P	A15			ALL
2534Z					BI	0-0	34-33-11	D41145P	PERG	1F		D43145P	PERG	1F		ALL
2535B		24		Y2	BJ	22-5	22-11-51	D43145P	B06			D41145P	B06			YC051-YC055
2535B		24		Y2	BJ	22-8	22-11-51	D43145P	B06			D41145P	B06			YC056-YR328
2535R		24		Y2	BJ	0-0	22-11-51	D43145P	B05			D41145P	B05			ALL
2535Z					BJ	0-0	22-11-51	D43145P	PERG	1F		D41145P	PERG	1F		ALL
2536B		24		Y2	BK	22-5	22-11-51	D43145P	B08			D41145P	B08			YC051-YC055
2536B		24		Y2	BK	22-8	22-11-51	D43145P	B08			D41145P	B08			YC056-YR328
2536R		24		Y2	BK	0-0	22-11-51	D43145P	B07			D41145P	B07			ALL
2536Z					BK	0-0	22-11-51	D43145P	PERG	1F		D41145P	PERG	1F		ALL
2537B		24		Y2	BL	22-5	22-11-51	D43145P	B10			D41145P	B10			YC051-YC055
2537B		24		Y2	BL	22-8	22-11-51	D43145P	B10			D41145P	B10			YC056-YR328
2537R		24		Y2	BL	0-0	22-11-51	D43145P	B09			D41145P	B09			ALL
2537Z					BL	0-0	22-11-51	D43145P	PERG	1F		D41145P	PERG	1F		ALL
2540B		24		Y2	BP	13-10	34-61-22	D45255J	A20			D41155P	A08			ALL
2540R		24		Y2	BP	0-0	34-61-22	D45255J	A19			D41155P	A07			ALL
2540Z					BP	0-0	34-61-22	D45255J	PERG	1F		D41155P	PERG	1F		ALL
2541B		24		Y2	BQ	13-10	34-61-22	D45255J	B06			D41155P	B08			ALL
2541R		24		Y2	BQ	0-0	34-61-22	D45255J	B05			D41155P	B07			ALL
2541Z					BQ	0-0	34-61-22	D45255J	PERG	1F		D41155P	PERG	1F		ALL
2542B		24		Y2	BR	13-10	34-61-22	D45255J	B10			D41155P	B16			ALL
2542R		24		Y2	BR	0-0	34-61-22	D45255J	B09			D41155P	B15			ALL
2542Z					BR	0-0	34-61-22	D45255J	PERG	1F		D41155P	PERG	1F		ALL
2543B		22		X2	BS	32-0	49-62-11	D45265J	A12			D43155P	B18			YC051-YC055
2543B		22		X2	BS	32-3	49-62-11	D45265J	A12			D43155P	B18			YC056-YR328
2543R		22		X2	BS	0-0	49-62-11	D45265J	A11			D43155P	B17			ALL
2543Z					BS	0-0	49-62-11	D45265J	PERG	1F		D43155P	PERG	1F		ALL
2545B		24		Y2	CA	22-8	34-61-14	D45265J	B13			D45023P	B01			YD158-YD170
2545R		24		Y2	CA	0-0	34-61-14	D45265J	A13			D45023P	A01			YD158-YD170
2545Z					CA	0-0	34-61-14	D45265J	PERG	1F		D45023P	PERG	1F		YD158-YD170
2546B		24		Y2	CB	22-8	34-61-15	D45265J	B14			D45023P	B02			YD158-YD170
2546R		24		Y2	CB	0-0	34-61-15	D45265J	A14			D45023P	A02			YD158-YD170
2546Z					CB	0-0	34-61-15	D45265J	PERG	1F		D45023P	PERG	1F		YD158-YD170
3501B		22		X3	HA	30-10	34-21-12	D03691	3			D45245J	A18			YC051-YC055
3501B		22		X3	HA	30-11	34-21-12	D03691	3			D45245J	A18			YC056-YR328
3501R		22		X3	HA	0-0	34-21-12	D03691	1			D45245J	A17			ALL
3501Y		22		X3	HA	0-0	34-21-12	D03691	5			D45245J	A19			ALL
3501Z					HA	0-0	34-21-12	D03691	PERB			D45245J	PERG	1F		ALL

WIRE LIST

D280A108

91-21-11

Section W5160

Page 21

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5162	286A5162				LEFT WING/BODY PRESSURE SEAL DISC TO E/E BAY											
0007	20		PA		2-6	36-11-11		D39921		2		GD00068	DC..	1		YC051-YL999, YR301-YR328
0007	20		PA		3-11	36-11-11		D39921		2		GD00068	DC..	1		YN231-YN501
0008	20		PA		2-6	73-21-12		D39921		9		GD00068	DC..	1		YC051-YL999, YR301-YR328
0008	20		PA		3-11	73-21-12		D39921		9		GD00068	DC..	1		YN231-YN501
0009	20		PA		2-6	78-35-11		D39921		13		GD00068	DC..	1		YC051-YL999, YR301-YR328
0009	20		PA		3-11	78-35-11		D39921		13		GD00068	DC..	1		YN231-YN501
0010	20		PA		2-6	30-11-11		D39921		16		GD00068	DC..	1		YC051-YL999, YR301-YR328
0010	20		PA		3-11	30-11-11		D39921		16		GD00068	DC..	1		YN231-YN501
0011	20		PA		2-6	78-36-11		D39921		17		GD00068	DC..	1		YC051-YL999, YR301-YR328
0011	20		PA		3-11	78-36-11		D39921		17		GD00068	DC..	1		YN231-YN501
0012	20		PA		2-6	36-11-11		D39921		29		GD00068	DC..	1		YC051-YL999, YR301-YR328
0012	20		PA		3-11	36-11-11		D39921		29		GD00068	DC..	1		YN231-YN501
0013	20		PA		2-6	78-36-11		D39921		39		GD00068	DC..	1		YC051-YL999, YR301-YR328
0013	20		PA		3-11	78-36-11		D39921		39		GD00068	DC..	1		YN231-YN501
1302	24		Y1	EN	44-8	73-21-12		D39921		21		D48134P	A02			YC051-YL999, YR301-YR328
1302	24		Y1	EN	34-10	73-21-12		D39921		21		D48134P	A02			YN231-YN501
1302Z				EN	0-0	73-21-12		D39921		S/R		D48134P	PERG	1F		ALL
2601B	20		X2	SA	35-0	SPARE		D39921		14		D40130P	A03			YC051-YC054, YC056-YL999, YR301-YR328
2601B	20		X2	SA	34-9	SPARE		D39921		14		D40130P	A03			YC055
2601B	20		X2	SA	25-2	SPARE		D39921		14		D40130P	A03			YN231-YN501
2601R	20		X2	SA	0-0	SPARE		D39921		5		D40130P	B03			ALL
2601Z				SA	0-0	SPARE		D39921		S/R		D40130P	PERG	1F		ALL
2602B	22		VX	SB	35-0	77-31-11		D39921		8		D40130P	A02			YC051-YC054, YC056-YL999, YR301-YR328
2602B	22		VX	SB	34-9	77-31-11		D39921		8		D40130P	A02			YC055
2602B	22		VX	SB	25-2	77-31-11		D39921		8		D40130P	A02			YN231-YN501
2602W	22		VX	SB	0-0	77-31-11		D39921		18		D40130P	B02			ALL
2602Z				SB	0-0	77-31-11		D39921		7		D40130P	B01			ALL

WIRE LIST

D280A108

91-21-11

Section W5160

Page 22

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5162	286A5162			LEFT WING/BODY PRESSURE SEAL DISC TO E/E BAY (continued)											
2603B	20	X2	SC		48-4	73-21-21	D39921		11		D11160		5		YC051-YL999, YR301-YR328
2603B	20	X2	SC		38-6	73-21-21	D39921		11		D11160		5		YN231-YN501
2603R	20	X2	SC		0-0	73-21-21	D39921		26		D11160		15		ALL
2603Z			SC		0-0	73-21-21	D39921		S/R		D11160		S/R		ALL
2604B	24	Y2	SD		35-0	73-24-11	D39921		34		D40130P		A05		YC051-YC054, YC056-YL999, YR301-YR328
2604B	24	Y2	SD		34-9	73-24-11	D39921		34		D40130P		A05		YC055
2604B	24	Y2	SD		25-2	73-24-11	D39921		34		D40130P		A05		YN231-YN501
2604R	24	Y2	SD		0-0	73-24-11	D39921		15		D40130P		B05		ALL
2604Z			SD		0-0	73-24-11	D39921		S/R		D40130P	PERG	1F		ALL
2605B	22	PB	SE		35-0	78-36-11	D39921		19		D40130P		A10		YC051-YC054, YC056-YL999, YR301-YR328
2605B	22	PB	SE		34-9	78-36-11	D39921		19		D40130P		A10		YC055
2605B	22	PB	SE		25-2	78-36-11	D39921		19		D40130P		A10		YN231-YN501
2605R	22	PB	SE		0-0	78-36-11	D39921		20		D40130P		B10		ALL
2606B	24	Y2	SF		35-0	73-21-11	D39921		23		D40130P		A06		YC051-YC054, YC056-YL999, YR301-YR328
2606B	24	Y2	SF		34-9	73-21-11	D39921		23		D40130P		A06		YC055
2606B	24	Y2	SF		25-2	73-21-11	D39921		23		D40130P		A06		YN231-YN501
2606R	24	Y2	SF		0-0	73-21-11	D39921		22		D40130P		B06		ALL
2606Z			SF		0-0	73-21-11	D39921		S/R		D40130P	PERG	1F		ALL
2607B	20	X2	SG		48-4	73-21-21	D39921		25		D11160		2		YC051-YL999, YR301-YR328
2607B	20	X2	SG		38-6	73-21-21	D39921		25		D11160		2		YN231-YN501
2607R	20	X2	SG		0-0	73-21-21	D39921		24		D11160		10		ALL
2607Z			SG		0-0	73-21-21	D39921		S/R		D11160		S/R		ALL
2608B	20	X2	SH		48-4	73-21-21	D39921		27		D11160		7		YC051-YL999, YR301-YR328
2608B	20	X2	SH		38-6	73-21-21	D39921		27		D11160		7		YN231-YN501
2608R	20	X2	SH		0-0	73-21-21	D39921		28		D11160		8		ALL
2608Z			SH		0-0	73-21-21	D39921		S/R		D11160		S/R		ALL
2609B	20	X2	SI		35-0	SPARE	D39921		31		D40130P		A09		YC051-YC054, YC056-YL999, YR301-YR328
2609B	20	X2	SI		34-9	SPARE	D39921		31		D40130P		A09		YC055

WIRE LIST

D280A108

91-21-11

Section W5160

Page 23

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5162	286A5162				LEFT WING/BODY PRESSURE SEAL DISC TO E/E BAY (continued)										
2609B	20	X2	SI		25-2	SPARE	D39921	31			D40130P	A09			YN231-YN501
2609R	20	X2	SI		0-0	SPARE	D39921	30			D40130P	B09			ALL
2609Z			SI		0-0	SPARE	D39921	S/R			D40130P	PERG	1F		ALL
2611B	24	Y2	SK		35-0	73-24-12	D39921	35			D40130P	A11			YC051-YC054, YC056-YL999, YR301-YR328
2611B	24	Y2	SK		34-9	73-24-12	D39921	35			D40130P	A11			YC055
2611B	24	Y2	SK		25-2	73-24-12	D39921	35			D40130P	A11			YN231-YN501
2611R	24	Y2	SK		0-0	73-24-12	D39921	36			D40130P	B11			ALL
2611Z			SK		0-0	73-24-12	D39921	S/R			D40130P	PERG	1F		ALL
2612B	22	PB	SL		35-0	78-36-11	D39921	38			D40130P	A12			YC051-YC054, YC056-YL999, YR301-YR328
2612B	22	PB	SL		34-9	78-36-11	D39921	38			D40130P	A12			YC055
2612B	22	PB	SL		25-2	78-36-11	D39921	38			D40130P	A12			YN231-YN501
2612R	22	PB	SL		0-0	78-36-11	D39921	37			D40130P	B12			ALL
5501	24	PK			35-0	36-11-11	D39921	10			D40130P	A13			YC051-YC054, YC056-YL999, YR301-YR328
5501	24	PK			34-9	36-11-11	D39921	10			D40130P	A13			YC055
5501	24	PK			25-2	36-11-11	D39921	10			D40130P	A13			YN231-YN501
5502	24	PK			35-0	36-11-11	D39921	3			D40130P	B13			YC051-YC054, YC056-YL999, YR301-YR328
5502	24	PK			34-9	36-11-11	D39921	3			D40130P	B13			YC055
5502	24	PK			25-2	36-11-11	D39921	3			D40130P	B13			YN231-YN501
5503	24	PK			35-0	36-11-11	D39921	12			D40130P	A14			YC051-YC054, YC056-YL999, YR301-YR328
5503	24	PK			34-9	36-11-11	D39921	12			D40130P	A14			YC055
5503	24	PK			25-2	36-11-11	D39921	12			D40130P	A14			YN231-YN501
6001	22	CQ			44-8	30-11-11	D39921	6			D48134P	A01			YC051-YL999, YR301-YR328
6001	22	CQ			34-10	30-11-11	D39921	6			D48134P	A01			YN231-YN501
6002	20	PA			44-8	78-35-11	D39921	4			D48134P	A03			YC051-YL999, YR301-YR328
6002	20	PA			34-10	78-35-11	D39921	4			D48134P	A03			YN231-YN501
6003	20	PA			3-6	73-21-21	D11160	13			GD00815	ST..	1A		ALL

WIRE LIST

D280A108

91-21-11
Section W5160
Page 24
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5163		286A5163			E1-1, E1-5, E3-1, E5-2										
0001	24	PK			24-2	22-31-52	D41157P	A11			D43157P	A05			YC051-YC055
0001	24	PK			24-4	22-31-52	D41157P	A11			D43157P	A05			YC056-YR328
0002	24	PK			24-10	31-62-25	D43157P	B02			D45247J	B08			YC051-YC055
0002	24	PK			25-0	31-62-25	D43157P	B02			D45247J	B08			YC056-YR328
0003	22	PA			9-10	34-21-21	D41157P	A17			D45257J	A14			ALL
0004	22	PA			9-10	SPARE	D41157P	A18			D45257J	A15			ALL
0005	20	PA			9-10	34-21-21	D41157P	A19			D45257J	A16			ALL
0006	20	PA			9-10	34-21-21	D41157P	A20			D45257J	A17			ALL
0007	20	CQ			9-10	34-21-21	D41157P	B01			D45257J	A18			ALL
0008	22	PA			9-10	34-61-12	D41157P	B04			D45257J	B07			ALL
0009	24	PK			24-11	31-62-25	D43157P	B01			D45257J	B09			YC051-YC055
0009	24	PK			25-1	31-62-25	D43157P	B01			D45257J	B09			YC056-YR328
0010	24	PK			24-10	31-62-25	D43157P	B11			D45247J	A01			YC051-YC055
0010	24	PK			25-0	31-62-25	D43157P	B11			D45247J	A01			YC056-YR328
0011	24	PK			24-10	31-62-25	D43157P	B12			D45247J	A02			YC051-YC055
0011	24	PK			25-0	31-62-25	D43157P	B12			D45247J	A02			YC056-YR328
0012	24	PK			24-10	31-62-25	D43157P	B13			D45247J	A03			YC051-YC055
0012	24	PK			25-0	31-62-25	D43157P	B13			D45247J	A03			YC056-YR328
0013	22	PA			24-10	SPARE	D45247J	A08			D43157P	A20			YC051-YC055
0013	22	PA			25-0	SPARE	D45247J	A08			D43157P	A20			YC056-YR328
0014	22	PA			0-7	34-21-22	D03697	17			D03697	14			ALL
0015	22	PA			0-7	34-21-22	D03697	20			D03697	13			ALL
0016	22	PA			0-7	34-21-22	D03697	9			D03697	12			ALL
0017	20	PA			2-8	34-21-22	D03697	18			GD00428	DC..	1		YC051-YC055
0017	20	PA			3-2	34-21-22	D03697	18			GD00428	DC..	1		YC056-YR328
0018	24	PK			24-2	22-31-52	D41157P	B18			D43157P	B20			YC051-YC055
0018	24	PK			24-4	22-31-52	D41157P	B18			D43157P	B20			YC056-YR328
0020	24	PK			24-3	34-45-11	D43147P	A05			D41157P	B09			YC051-YC055
0020	24	PK			24-5	34-45-11	D43147P	A05			D41157P	B09			YC056-YR328
0021	20	PA			24-11	SPARE	D43147P	A01			D45247J	A16			YC051-YC055
0021	20	PA			25-1	SPARE	D43147P	A01			D45247J	A16			YC056-YR328
0022	20	PA			24-11	SPARE	D43147P	A02			D45247J	A17			YC051-YC055
0022	20	PA			25-1	SPARE	D43147P	A02			D45247J	A17			YC056-YD157
0023	20	PA			24-11	SPARE	D43147P	A12			D45247J	A18			YC051-YC055
0023	20	PA			25-1	SPARE	D43147P	A12			D45247J	A18			YC056-YD157
0024	16	PA			9-4	23-12-21	D41147P	F			D41557J	21			ALL
0025	16	PA			9-4	23-12-21	D41147P	G			D41557J	23			YC051-YD157
0025	16	PA			9-4	SPARE	D41147P	G			D41557J	23			YD158-YR328
0026	20	PA			24-11	34-61-11	D43147P	A13			D45247J	A19			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5160

Page 25

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5163	286A5163				E1-1, E1-5, E3-1, E5-2 (continued)										
0026	20		PA		25-1	34-61-11	D43147P		A13		D45247J	A19			YC056-YR328
0027	20		PA		24-11	34-61-11	D43147P		A14		D45247J	A20			YC051-YC055
0027	20		PA		25-1	34-61-11	D43147P		A14		D45247J	A20			YC056-YR328
0028	24		PK		24-11	73-21-31	D45247J		B01		D43147P	A16			YC051-YC055
0028	24		PK		25-1	73-21-31	D45247J		B01		D43147P	A16			YC056-YR328
0029	24		PK		24-11	73-21-31	D45247J		B02		D43147P	A17			YC051-YC055
0029	24		PK		25-1	73-21-31	D45247J		B02		D43147P	A17			YC056-YR328
0030	24		PK		24-11	73-21-31	D45247J		B03		D43147P	A18			YC051-YC055
0030	24		PK		25-1	73-21-31	D45247J		B03		D43147P	A18			YC056-YR328
0031	22		PA		3-1	34-51-41	D41157P		B16		D02127	E			ALL
0032	22		PA		3-1	34-51-41	D41157P		B17		D02127	D			ALL
0033	22		PA		9-4	34-51-41	D41557J		3		D41157P	A16			ALL
0034	22		PA		9-4	34-51-41	D41557J		12		D41157P	B06			ALL
0035	22		PA		9-4	SPARE	D41157P		B05		D41557J	4			ALL
0036	22		PA		3-1	34-51-41	D02127		A		D41147P	A08			ALL
0037	22		PA		1-3	34-51-41	D02127		C		GD00317	DC..	E		ALL
0038	22		PA		9-10	34-21-16	D41157P		B19		D45257J	A08			ALL
0039	22		PA		9-10	SPARE	D45257J		A07		D41157P	B20			ALL
0040	24		PK		24-3	SPARE	D43147P		A07		D41147P	A07			YC051-YC055
0040	24		PK		24-5	SPARE	D43147P		A07		D41147P	A07			YC056-YR328
0041	22		PA		9-4	23-51-51	D41557J		7		D41147P	A09			ALL
2501B	24		Y2	AA	9-10	SPARE	D45257J		A02		D41157P	A02			YC051-YD157, YL951-YR328
2501B	24		Y2	AA	9-10	MULTI	D45257J		A02		D41157P	A02			YD158-YD170
2501R	24		Y2	AA	0-0	SPARE	D45257J		A01		D41157P	A01			YC051-YD157, YL951-YR328
2501R	24		Y2	AA	0-0	MULTI	D45257J		A01		D41157P	A01			YD158-YD170
2501Z				AA	0-0	SPARE	D45257J	PERG	1F		D41157P	PERG	1F		YC051-YD157, YL951-YR328
2501Z				AA	0-0	MULTI	D45257J	PERG	1F		D41157P	PERG	1F		YD158-YD170
2502B	24		Y2	AB	9-9	34-21-24	D45247J		B07		D41157P	A04			ALL
2502R	24		Y2	AB	0-0	34-21-24	D45247J		B06		D41157P	A03			ALL
2502Z				AB	0-0	34-21-24	D45247J	PERG	1F		D41157P	PERG	1F		ALL
2503B	24		Y2	AC	24-2	73-24-21	D43157P		A02		D41157P	A06			YC051-YC055
2503B	24		Y2	AC	24-4	73-24-21	D43157P		A02		D41157P	A06			YC056-YR328
2503R	24		Y2	AC	0-0	73-24-21	D43157P		A01		D41157P	A05			ALL
2503Z				AC	0-0	73-24-21	D43157P	PERG	1F		D41157P	PERG	1F		ALL
2504B	24		Y2	AD	24-2	22-31-52	D43157P		A04		D41157P	A08			YC051-YC055
2504B	24		Y2	AD	24-4	22-31-52	D43157P		A04		D41157P	A08			YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W5160

Page 26

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5163	286A5163			E1-1, E1-5, E3-1, E5-2 (continued)											
2504R	24	Y2	AD		0-0	22-31-52	D43157P	A03			D41157P	A07			ALL
2504Z			AD		0-0	22-31-52	D43157P	PERG	1F		D41157P	PERG	1F		ALL
2505B	24	Y2	AE		24-2	22-31-52	D41157P	A10			D43157P	A07			YC051-YC055
2505B	24	Y2	AE		24-4	22-31-52	D41157P	A10			D43157P	A07			YC056-YR328
2505R	24	Y2	AE		0-0	22-31-52	D41157P	A09			D43157P	A06			ALL
2505Z			AE		0-0	22-31-52	D41157P	PERG	1F		D43157P	PERG	1F		ALL
2506B	24	Y2	AF		25-0	34-21-24	D43147P	B04			D45257J	A06			YC051-YC055
2506B	24	Y2	AF		25-2	34-21-24	D43147P	B04			D45257J	A06			YC056-YR328
2506R	24	Y2	AF		0-0	34-21-24	D43147P	B03			D45257J	A05			ALL
2506Z			AF		0-0	34-21-24	D43147P	PERG	1F		D45257J	PERG	1F		ALL
2508B	24	Y2	AH		24-11	SPARE	D43157P	A09			D45257J	A10			YC051-YC055
2508B	24	Y2	AH		25-1	SPARE	D43157P	A09			D45257J	A10			YC056-YD157, YL951-YR328
2508B	24	Y2	AH		13-10	34-61-14	D45025P	B01			D45257J	A10			YD158-YD170
2508R	24	Y2	AH		0-0	SPARE	D43157P	A08			D45257J	A09			YC051-YD157, YL951-YR328
2508R	24	Y2	AH		0-0	34-61-14	D45025P	A01			D45257J	A09			YD158-YD170
2508Z			AH		0-0	SPARE	D43157P	PERG	1F		D45257J	PERG	1F		YC051-YD157, YL951-YR328
2508Z			AH		0-0	34-61-14	D45025P	PERG	1F		D45257J	PERG	1F		YD158-YD170
2509B	24	Y2	AI		24-11	SPARE	D43157P	A11			D45257J	A12			YC051-YC055
2509B	24	Y2	AI		25-1	SPARE	D43157P	A11			D45257J	A12			YC056-YD157, YL951-YR328
2509B	24	Y2	AI		13-10	34-61-15	D45025P	B02			D45257J	A12			YD158-YD170
2509R	24	Y2	AI		0-0	SPARE	D43157P	A10			D45257J	A11			YC051-YD157, YL951-YR328
2509R	24	Y2	AI		0-0	34-61-15	D45025P	A02			D45257J	A11			YD158-YD170
2509Z			AI		0-0	SPARE	D43157P	PERG	1F		D45257J	PERG	1F		YC051-YD157, YL951-YR328
2509Z			AI		0-0	34-61-15	D45025P	PERG	1F		D45257J	PERG	1F		YD158-YD170
2510B	24	Y2	AJ		13-4	34-21-24	D41557J	9			D45247J	B05			ALL
2510R	24	Y2	AJ		0-0	34-21-24	D41557J	8			D45247J	B04			ALL
2510Z			AJ		0-0	34-21-24	D41557J	S/R			D45247J	PERG	1F		ALL
2511B	24	Y2	AK		25-0	34-21-24	D43147P	B02			D45257J	A04			YC051-YC055
2511B	24	Y2	AK		25-2	34-21-24	D43147P	B02			D45257J	A04			YC056-YR328
2511R	24	Y2	AK		0-0	34-21-24	D43147P	B01			D45257J	A03			ALL
2511Z			AK		0-0	34-21-24	D43147P	PERG	1F		D45257J	PERG	1F		ALL
2512B	24	Y2	AL		9-10	34-21-23	D41157P	B03			D45257J	B02			ALL
2512R	24	Y2	AL		0-0	34-21-23	D41157P	B02			D45257J	B01			ALL

WIRE LIST

D280A108

91-21-11

Section W5160

Page 27

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W5163	286A5163				E1-1, E1-5, E3-1, E5-2 (continued)												
2512Z				AL	0-0	34-21-23	D41157P	PERG	1F		D45257J	PERG	1F		ALL		
2513B	24	Y2	AM		24-11	34-21-23	D43157P	A13			D45257J	B04			YC051-YC055		
2513B	24	Y2	AM		25-1	34-21-23	D43157P	A13			D45257J	B04			YC056-YR328		
2513R	24	Y2	AM		0-0	34-21-23	D43157P	A12			D45257J	B03			ALL		
2513Z				AM	0-0	34-21-23	D43157P	PERG	1F		D45257J	PERG	1F		ALL		
2514B	24	Y2	AN		24-11	34-21-23	D43157P	A15			D45257J	B06			YC051-YC055		
2514B	24	Y2	AN		25-1	34-21-23	D43157P	A15			D45257J	B06			YC056-YR328		
2514R	24	Y2	AN		0-0	34-21-23	D43157P	A14			D45257J	B05			ALL		
2514Z				AN	0-0	34-21-23	D43157P	PERG	1F		D45257J	PERG	1F		ALL		
2516B	22	X2	AQ		24-11	34-61-15	D43157P	A17			D45257J	B12			YC051-YC055		
2516B	22	X2	AQ		25-1	34-61-15	D43157P	A17			D45257J	B12			YC056-YR328		
2516R	22	X2	AQ		0-0	34-61-15	D43157P	A16			D45257J	B11			ALL		
2516Z				AQ	0-0	34-61-15	D43157P	PERG	1F		D45257J	PERG	1F		ALL		
2517B	22	X2	AR		24-11	34-61-15	D43157P	A19			D45257J	B14			YC051-YC055		
2517B	22	X2	AR		25-1	34-61-15	D43157P	A19			D45257J	B14			YC056-YR328		
2517R	22	X2	AR		0-0	34-61-15	D43157P	A18			D45257J	B13			ALL		
2517Z				AR	0-0	34-61-15	D43157P	PERG	1F		D45257J	PERG	1F		ALL		
2518B	24	Y2	AS		13-4	34-21-23	D41557J	18			D45247J	A18			YD158-YR328		
2518R	24	Y2	AS		0-0	34-21-23	D41557J	17			D45247J	A17			YD158-YR328		
2518Z				AS	0-0	34-21-23	D41557J	S/R			D45247J	PERG	1F		YD158-YR328		
2519B	24	Y2	AT		24-11	31-62-25	D43157P	B04			D45257J	B16			YC051-YC055		
2519B	24	Y2	AT		25-1	31-62-25	D43157P	B04			D45257J	B16			YC056-YR328		
2519R	24	Y2	AT		0-0	31-62-25	D43157P	B03			D45257J	B15			ALL		
2519Z				AT	0-0	31-62-25	D43157P	PERG	1F		D45257J	PERG	1F		ALL		
2520B	24	Y2	AU		24-11	31-62-25	D43157P	B06			D45257J	B18			YC051-YC055		
2520B	24	Y2	AU		25-1	31-62-25	D43157P	B06			D45257J	B18			YC056-YR328		
2520R	24	Y2	AU		0-0	31-62-25	D43157P	B05			D45257J	B17			ALL		
2520Z				AU	0-0	31-62-25	D43157P	PERG	1F		D45257J	PERG	1F		ALL		
2521B	24	Y2	AV		24-11	31-62-25	D43157P	B08			D45257J	B20			YC051-YC055		
2521B	24	Y2	AV		25-1	31-62-25	D43157P	B08			D45257J	B20			YC056-YR328		
2521R	24	Y2	AV		0-0	31-62-25	D43157P	B07			D45257J	B19			ALL		
2521Z				AV	0-0	31-62-25	D43157P	PERG	1F		D45257J	PERG	1F		ALL		
2522B	24	Y2	AW		24-3	31-62-25	D43157P	B10			D41147P	A02			YC051-YC055		
2522B	24	Y2	AW		24-4	31-62-25	D43157P	B10			D41147P	A02			YC056-YR328		
2522R	24	Y2	AW		0-0	31-62-25	D43157P	B09			D41147P	A01			ALL		
2522Z				AW	0-0	31-62-25	D43157P	PERG	1F		D41147P	PERG	1F		ALL		
2523B	24	Y2	AX		24-10	31-62-25	D43157P	B15			D45247J	A05			YC051-YC055		
2523B	24	Y2	AX		25-0	31-62-25	D43157P	B15			D45247J	A05			YC056-YR328		
2523R	24	Y2	AX		0-0	31-62-25	D43157P	B14			D45247J	A04			ALL		

WIRE LIST

D280A108

91-21-11

Section W5160

Page 28

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice
W5163	286A5163				E1-1, E1-5, E3-1, E5-2 (continued)										
2523Z				AX	0-0	31-62-25	D43157P	PERG	1F		D45247J	PERG	1F	ALL	
2524B	24	Y2	AY		24-10	31-62-25	D43157P	B17			D45247J	A07		YC051-YC055	
2524B	24	Y2	AY		25-0	31-62-25	D43157P	B17			D45247J	A07		YC056-YR328	
2524R	24	Y2	AY		0-0	31-62-25	D43157P	B16			D45247J	A06		ALL	
2524Z			AY		0-0	31-62-25	D43157P	PERG	1F		D45247J	PERG	1F	ALL	
2525B	24	Y2	AZ		24-3	31-62-25	D43157P	B19			D41147P	A06		YC051-YC055	
2525B	24	Y2	AZ		24-4	31-62-25	D43157P	B19			D41147P	A06		YC056-YR328	
2525R	24	Y2	AZ		0-0	31-62-25	D43157P	B18			D41147P	A05		ALL	
2525Z			AZ		0-0	31-62-25	D43157P	PERG	1F		D41147P	PERG	1F	ALL	
2526B	24	Y2	BA		27-1	34-21-22	D03697	8			D45247J	A13		YC051-YC055	
2526B	24	Y2	BA		26-11	34-21-22	D03697	8			D45247J	A13		YC056-YR328	
2526R	24	Y2	BA		0-0	34-21-22	D03697	7			D45247J	A12		ALL	
2526Z			BA		0-0	34-21-22	D03697	PERB			D45247J	PERG	1F	ALL	
2527B	24	Y2	BB		24-11	34-61-14	D43147P	B06			D45247J	B12		YC051-YC055	
2527B	24	Y2	BB		25-1	34-61-14	D43147P	B06			D45247J	B12		YC056-YR328	
2527R	24	Y2	BB		0-0	34-61-14	D43147P	B05			D45247J	B11		ALL	
2527Z			BB		0-0	34-61-14	D43147P	PERG	1F		D45247J	PERG	1F	ALL	
2528B	24	Y2	BC		24-3	34-45-11	D43147P	A04			D41157P	B08		YC051-YC055	
2528B	24	Y2	BC		24-5	34-45-11	D43147P	A04			D41157P	B08		YC056-YR328	
2528R	24	Y2	BC		0-0	34-45-11	D43147P	A03			D41157P	B07		ALL	
2528Z			BC		0-0	34-45-11	D43147P	PERG	1F		D41157P	PERG	1F	ALL	
2529B	24	Y2	BD		24-3	SPARE	D41157P	B11			D43147P	A20		YC051-YC055	
2529B	24	Y2	BD		24-5	SPARE	D41157P	B11			D43147P	A20		YC056-YR328	
2529R	24	Y2	BD		0-0	SPARE	D41157P	B10			D43147P	A19		ALL	
2529Z			BD		0-0	SPARE	D41157P	PERG	1F		D43147P	PERG	1F	ALL	
2530B	24	Y2	BE		24-3	SPARE	D41157P	B13			D43147P	A09		YC051-YC055	
2530B	24	Y2	BE		24-5	SPARE	D41157P	B13			D43147P	A09		YC056-YD157	
2530R	24	Y2	BE		0-0	SPARE	D41157P	B12			D43147P	A08		YC051-YD157	
2530Z			BE		0-0	SPARE	D41157P	PERG	1F		D43147P	PERG	1F	YC051-YD157	
2531B	24	Y2	BF		24-3	34-49-11	D43147P	A11			D41157P	B15		YC051-YC055	
2531B	24	Y2	BF		24-5	34-49-11	D43147P	A11			D41157P	B15		YC056-YR328	
2531R	24	Y2	BF		0-0	34-49-11	D43147P	A10			D41157P	B14		ALL	
2531Z			BF		0-0	34-49-11	D43147P	PERG	1F		D41157P	PERG	1F	ALL	
2532B	24	Y2	BG		13-4	34-55-21	D45247J	A15			D41557J	6		ALL	
2532R	24	Y2	BG		0-0	34-55-21	D45247J	A14			D41557J	5		ALL	
2532Z			BG		0-0	34-55-21	D45247J	PERG	1F		D41557J	S/R		ALL	
2533B	24	Y2	BH		9-4	34-45-21	D41557J	14			D41157P	A13		ALL	
2533R	24	Y2	BH		0-0	34-45-21	D41557J	13			D41157P	A12		ALL	
2533Z			BH		0-0	34-45-21	D41557J	S/R			D41157P	PERG	1F	ALL	

WIRE LIST

D280A108

91-21-11

Section W5160

Page 29

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5163	286A5163				E1-1, E1-5, E3-1, E5-2 (continued)										
2534B	24		Y2	BI	9-4	34-45-21	D41557J		2		D41157P	A15			ALL
2534R	24		Y2	BI	0-0	34-45-21	D41557J		1		D41157P	A14			ALL
2534Z				BI	0-0	34-45-21	D41557J		S/R		D41157P	PERG	1F		ALL
2535B	24		Y2	BJ	13-4	34-61-14	D41557J		16		D45247J	B10			ALL
2535R	24		Y2	BJ	0-0	34-61-14	D41557J		15		D45247J	B09			ALL
2535Z				BJ	0-0	34-61-14	D41557J		S/R		D45247J	PERG	1F		ALL
2536B	24		Y2	BK	24-11	34-21-14	D45247J		B14		D43147P	B08			YC053-YC055
2536B	24		Y2	BK	25-1	34-21-14	D45247J		B14		D43147P	B08			YC056-YR328
2536R	24		Y2	BK	0-0	34-21-14	D45247J		B13		D43147P	B07			YC053-YR328
2536Z				BK	0-0	34-21-14	D45247J	PERG	1F		D43147P	PERG	1F		YC053-YR328
2537B	24		Y2	BL	9-10	34-21-24	D45247J		B16		D41147P	A04			YC053-YR328
2537R	24		Y2	BL	0-0	34-21-24	D45247J		B15		D41147P	A03			YC053-YR328
2537Z				BL	0-0	34-21-24	D45247J	PERG	1F		D41147P	PERG	1F		YC053-YR328
2538B	24		Y2	BM	24-11	34-21-24	D45247J		B18		D43147P	B10			YC053-YC055
2538B	24		Y2	BM	25-1	34-21-24	D45247J		B18		D43147P	B10			YC056-YR328
2538R	24		Y2	BM	0-0	34-21-24	D45247J		B17		D43147P	B09			YC053-YR328
2538Z				BM	0-0	34-21-24	D45247J	PERG	1F		D43147P	PERG	1F		YC053-YR328
2541B	24		Y2	BQ	9-4	22-11-51	D41557J		30		D41157P	B13			YD158-YR328
2541R	24		Y2	BQ	0-0	22-11-51	D41557J		29		D41157P	B12			YD158-YR328
2541Z				BQ	0-0	22-11-51	D41557J		S/R		D41157P	PERG	1F		YD158-YR328
2542B	24		Y2	BR	9-10	34-21-24	D41147P		B08		D45247J	B20			YD158-YR328
2542R	24		Y2	BR	0-0	34-21-24	D41147P		B06		D45247J	B19			YD158-YR328
2542Z				BR	0-0	34-21-24	D41147P	PERG	1F		D45247J	PERG	1F		YD158-YR328
3501B	22		X3	HA	27-1	34-21-22	D03697		3		D45247J	A10			YC051-YC055
3501B	22		X3	HA	26-11	34-21-22	D03697		3		D45247J	A10			YC056-YR328
3501R	22		X3	HA	0-0	34-21-22	D03697		1		D45247J	A09			ALL
3501Y	22		X3	HA	0-0	34-21-22	D03697		5		D45247J	A11			ALL
3501Z				HA	0-0	34-21-22	D03697	PERB			D45247J	PERG	1F		ALL
W5164	286A5164				LEFT WING PRESS SEAL CONN TO E/E BAY										
0501	22		CQ		44-10	29-11-11	D39933		30		D40718P	A01			YC051-YC055
0501	22		CQ		44-11	29-11-11	D39933		30		D40718P	A01			YC056-YD153
0501	22		CQ		44-11	29-11-11	D39933		18		D40718P	A01			YD154-YL999, YR301-YR328
0501	22		CQ		35-0	29-11-11	D39933		18		D40718P	A01			YN231-YN236, YN501
1101	18		X1	BN	44-10	24-11-11	D39933		10		D40718P	F			YC051-YC055
1101	18		X1	BN	44-11	24-11-11	D39933		10		D40718P	F			YC056-YL999, YR301-YR328
1101	18		X1	BN	35-0	24-11-11	D39933		10		D40718P	F			YN231-YN236, YN501

WIRE LIST

D280A108

91-21-11

Section W5160

Page 30

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5164		286A5164				LEFT WING PRESS SEAL CONN TO E/E BAY (continued)										
1101Z					BN	0-0	24-11-11	D39933		S/R		D40718P	PERG	1F		YC051-YN236, YN501-YR328
1301	20	X1			EN	43-4	28-21-11	D40718P		B08		SP00202		S		YC051-YC055
1301	20	X1			EN	43-6	28-21-11	D40718P		B08		SP00202		S		YC056-YL999, YR301-YR328
1301	20	X1			EN	34-1	28-21-11	D40718P		B08		SP00202		S		YN231-YN236, YN501
1301Z					EN	0-0	28-21-11	D40718P		PERG	1F	SP00202		DED		YC051-YN236, YN501-YR328
2201B	20	X2			KA	44-9	24-21-11	D39933		38		D40132P		K		YC051-YC055
2201B	20	X2			KA	44-11	24-21-11	D39933		38		D40132P		K		YC056-YL999, YR301-YR328
2201B	20	X2			KA	35-0	24-21-11	D39933		38		D40132P		K		YN231-YN236, YN501
2201R	20	X2			KA	0-0	24-21-11	D39933		37		D40132P		J		YC051-YN236, YN501-YR328
2201Z					KA	0-0	24-21-11	D39933		36		D40132P		B10		YC051-YN236, YN501-YR328
2202B	22	PB			KB	44-9	24-11-11	D39933		39		D40132P		B03		YC051-YC055
2202B	22	PB			KB	44-11	24-11-11	D39933		39		D40132P		B03		YC056-YL999, YR301-YR328
2202B	22	PB			KB	35-0	24-11-11	D39933		39		D40132P		B03		YN231-YN236, YN501
2202R	22	PB			KB	0-0	24-11-11	D39933		19		D40132P		A03		YC051-YN236, YN501-YR328
2602B	20	X2			SB	44-10	SPARE	D39933		26		D40718P		A05		YC051-YC055
2602B	20	X2			SB	44-11	SPARE	D39933		26		D40718P		A05		YC056-YL999, YR301-YR328
2602B	20	X2			SB	35-0	SPARE	D39933		26		D40718P		A05		YN231-YN236, YN501
2602R	20	X2			SB	0-0	SPARE	D39933		25		D40718P		B05		YC051-YN236, YN501-YR328
2602Z					SB	0-0	SPARE	D39933		S/R		D40718P		PERG	1F	YC051-YN236, YN501-YR328
3201B	18	X3			YA	44-9	24-21-11	D39933		17		D40132P		G		YC051-YC055
3201B	18	X3			YA	44-11	24-21-11	D39933		17		D40132P		G		YC056-YD153
3201B	18	X3			YA	44-11	24-21-11	D39933		12		D40132P		G		YD154-YL999, YR301-YR328
3201B	18	X3			YA	35-0	24-21-11	D39933		12		D40132P		G		YN231-YN236, YN501
3201R	18	X3			YA	0-0	24-21-11	D39933		6		D40132P		F		YC051-YD153
3201R	18	X3			YA	0-0	24-21-11	D39933		1		D40132P		F		YD154-YN236, YN501-YR328
3201Y	18	X3			YA	0-0	24-21-11	D39933		16		D40132P		H		YC051-YD153

WIRE LIST

D280A108

91-21-11

Section W5160

Page 31

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5164	286A5164				LEFT WING PRESS SEAL CONN TO E/E BAY (continued)										
3201Y	18	X3	YA		0-0	24-21-11	D39933		14		D40132P	H			YD154-YN236, YN501-YR328
3201Z			YA		0-0	24-21-11	D39933		5		D40132P	A10			YC051-YN236, YN501-YR328
4101B	20	X4	N6		44-9	24-24-11	D39933		33		D40132P	A02			YC051-YC055
4101B	20	X4	N6		44-11	24-24-11	D39933		33		D40132P	A02			YC056-YD153
4101B	20	X4	N6		44-11	24-24-11	D39933		15		D40132P	A02			YD154-YL999, YR301-YR328
4101B	20	X4	N6		35-0	24-24-11	D39933		15		D40132P	A02			YN231-YN236, YN501
4101G	20	X4	N6		0-0	24-24-11	D39933		15		D40132P	A01			YC051-YD153
4101G	20	X4	N6		0-0	24-24-11	D39933		33		D40132P	A01			YD154-YN236, YN501-YR328
4101R	20	X4	N6		0-0	24-24-11	D39933		34		D40132P	B02			YC051-YD153
4101R	20	X4	N6		0-0	24-24-11	D39933		35		D40132P	B02			YD154-YN236, YN501-YR328
4101Y	20	X4	N6		0-0	24-24-11	D39933		35		D40132P	B01			YC051-YD153
4101Y	20	X4	N6		0-0	24-24-11	D39933		32		D40132P	B01			YD154-YN236, YN501-YR328
4101Z			N6		0-0	24-24-11	D39933		S/R		D40132P	PERG	1F		YC051-YN236, YN501-YR328
W5166	286A5166				LEFT WING BODY PRESS SEAL TO E1-1										
2202B	24	PL	KB		45-5	27-81-12	D39901		19		D40122P	A01			YC051-YL999, YR301-YR328
2202B	24	PL	KB		36-2	27-81-12	D39901		19		D40122P	A01			YN231-YN501
2202R	24	PL	KB		0-0	27-81-12	D39901		8		D40122P	B01			ALL
2204B	24	PL	KD		45-5	27-81-12	D39901		18		D40122P	A02			YC051-YL999, YR301-YR328
2204B	24	PL	KD		36-2	27-81-12	D39901		18		D40122P	A02			YN231-YN501
2204R	24	PL	KD		0-0	27-81-12	D39901		39		D40122P	B02			ALL
2205B	24	PL	KE		45-5	27-81-12	D39901		21		D40122P	A03			YC051-YL999, YR301-YR328
2205B	24	PL	KE		36-2	27-81-12	D39901		21		D40122P	A03			YN231-YN501
2205R	24	PL	KE		0-0	27-81-12	D39901		20		D40122P	B03			ALL
2206B	24	PL	KF		45-5	27-81-12	D39901		23		D40122P	A04			YC051-YL999, YR301-YR328
2206B	24	PL	KF		36-2	27-81-12	D39901		23		D40122P	A04			YN231-YN501
2206R	24	PL	KF		0-0	27-81-12	D39901		22		D40122P	B04			ALL

WIRE LIST

D280A108

91-21-11

Section W5160

Page 32

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From			To			Effectivity		
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W5166	286A5166			LEFT WING BODY PRESS SEAL TO E1-1 (continued)										
2207B	24	PL	KG	45-5	27-81-12	D39901	25			D40122P	A05		YC051-YL999, YR301-YR328	
2207B	24	PL	KG	36-2	27-81-12	D39901	25			D40122P	A05		YN231-YN501	
2207R	24	PL	KG	0-0	27-81-12	D39901	24			D40122P	B05		ALL	
2208B	24	PL	KH	45-5	27-81-12	D39901	28			D40122P	A06		YC051-YL999, YR301-YR328	
2208B	24	PL	KH	36-2	27-81-12	D39901	28			D40122P	A06		YN231-YN501	
2208R	24	PL	KH	0-0	27-81-12	D39901	27			D40122P	B06		ALL	
2211B	24	PL	KK	45-5	27-81-12	D39901	36			D40122P	A07		YC051-YL999, YR301-YR328	
2211B	24	PL	KK	36-2	27-81-12	D39901	36			D40122P	A07		YN231-YN501	
2211R	24	PL	KK	0-0	27-81-12	D39901	35			D40122P	B07		ALL	
2212B	24	PL	KL	45-5	27-81-12	D39901	38			D40122P	A08		YC051-YL999, YR301-YR328	
2212B	24	PL	KL	36-2	27-81-12	D39901	38			D40122P	A08		YN231-YN501	
2212R	24	PL	KL	0-0	27-81-12	D39901	37			D40122P	B08		ALL	
2213B	24	PL	KM	45-5	27-81-12	D39901	12			D40122P	B11		YC051-YL999, YR301-YR328	
2213B	24	PL	KM	36-2	27-81-12	D39901	12			D40122P	B11		YN231-YN501	
2213R	24	PL	KM	0-0	27-81-12	D39901	11			D40122P	A11		ALL	
2214B	24	PL	KN	45-5	27-81-12	D39901	16			D40122P	B12		YC051-YL999, YR301-YR328	
2214B	24	PL	KN	36-2	27-81-12	D39901	16			D40122P	B12		YN231-YN501	
2214R	24	PL	KN	0-0	27-81-12	D39901	15			D40122P	A12		ALL	
2215B	24	PL	KP	45-5	27-81-12	D39901	30			D40122P	B13		YC051-YL999, YR301-YR328	
2215B	24	PL	KP	36-2	27-81-12	D39901	30			D40122P	B13		YN231-YN501	
2215R	24	PL	KP	0-0	27-81-12	D39901	29			D40122P	A13		ALL	
6004R	20	PH		45-5	26-12-11	D39901	14			D40122P	A09		YC051-YD153	
6004R	20	PH		45-5	26-12-11	D39901	1			D40122P	A09		YD154-YL999, YR301-YR328	
6004R	20	PH		36-2	26-12-11	D39901	1			D40122P	A09		YN231-YN501	
6005	22	PA		45-5	30-11-11	D39901	10			D40122P	B09		YC051-YD153	
6005	22	PA		45-5	30-11-11	D39901	2			D40122P	B09		YD154-YL999, YR301-YR328	
6005	22	PA		36-2	30-11-11	D39901	2			D40122P	B09		YN231-YN501	

WIRE LIST

D280A108

91-21-11

Section W5160

Page 33

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5168	286A5168				LEFT WING/BODY PRESS SEAL TO E/E BAY										
1301	20	X1	EN		34-9	73-22-11	D39929		7		D40138P	A07			YC051-YL999, YR301-YR328
1301	20	X1	EN		24-9	73-22-11	D39929		7		D40138P	A07			YN231-YN501
1301Z			EN		0-0	73-22-11	D39929		S/R		D40138P	PERG	1F		ALL
1302	20	X1	EP		34-9	74-11-11	D39929		11		D40138P	A01			YC051-YD153
1302	20	X1	EP		34-9	74-11-11	D39929		6		D40138P	A01			YD154-YL999, YR301-YR328
1302	20	X1	EP		24-9	74-11-11	D39929		6		D40138P	A01			YN231-YN501
1302Z			EP		0-0	74-11-11	D39929		S/R		D40138P	PERG	1F		ALL
2601B	20	X2	SA		34-9	SPARE	D39929		2		D40138P	A02			YC051-YL999, YR301-YR328
2601B	20	X2	SA		24-9	SPARE	D39929		2		D40138P	A02			YN231-YN501
2601R	20	X2	SA		0-0	SPARE	D39929		3		D40138P	B02			ALL
2601Z			SA		0-0	SPARE	D39929		S/R		D40138P	PERG	1F		ALL
2602B	20	X2	SB		34-9	SPARE	D39929		4		D40138P	A03			YC051-YL999, YR301-YR328
2602B	20	X2	SB		24-9	SPARE	D39929		4		D40138P	A03			YN231-YN501
2602R	20	X2	SB		0-0	SPARE	D39929		5		D40138P	B03			ALL
2602Z			SB		0-0	SPARE	D39929		S/R		D40138P	PERG	1F		ALL
6003R	20	PH			34-9	26-11-11	D39929		9		D40138P	A04			YC051-YL999, YR301-YR328
6003R	20	PH			24-9	26-11-11	D39929		9		D40138P	A04			YN231-YN501
6004R	20	PH			34-9	26-11-11	D39929		10		D40138P	B04			YC051-YL999, YR301-YR328
6004R	20	PH			24-9	26-11-11	D39929		10		D40138P	B04			YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W5160

Page 34 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type
W5170	286A5170				LEFT WING/BODY PRESS SEAL TO E/E BAY										
0501	20		PA		29-6	29-31-11	D40734J	18			D40266P	4		YC051-YL999, YR301-YR328	
0501	20		PA		19-8	29-31-11	D40734J	18			D40266P	4		YN231-YN501	
0502	20		PA		29-6	29-31-11	D40734J	19			D40266P	5		YC051-YL999, YR301-YR328	
0502	20		PA		19-8	29-31-11	D40734J	19			D40266P	5		YN231-YN501	
0503	20		PA		29-6	29-31-11	D40734J	20			D40266P	6		YC051-YL999, YR301-YR328	
0503	20		PA		19-8	29-31-11	D40734J	20			D40266P	6		YN231-YN501	
0504	20		CQ		43-1	27-23-11	TB0262X	A002	1A		D40266P	1		YC051-YC052	
0504	20		CQ		43-6	27-23-11	TB0262X	A002	1A		D40266P	1		YC053-YL999, YR301-YR328	
0504	20		CQ		33-8	27-23-11	TB0262X	A002	1A		D40266P	1		YN231-YN501	
0505	20		CQ		43-1	27-23-11	TB0262X	A003	1A		D40266P	2		YC051-YC052	
0505	20		CQ		43-6	27-23-11	TB0262X	A003	1A		D40266P	2		YC053-YL999, YR301-YR328	
0505	20		CQ		33-8	27-23-11	TB0262X	A003	1A		D40266P	2		YN231-YN501	
0506	22		CQ		43-1	27-23-14	TB0262X	B003	1A		D40266P	3		YC051-YC052	
0506	22		CQ		43-6	27-23-14	TB0262X	B003	1A		D40266P	3		YC053-YL999, YR301-YR328	
0506	22		CQ		33-8	27-23-14	TB0262X	B003	1A		D40266P	3		YN231-YN501	
1301	20	X1	EN		67-10	74-11-11	D39925	3			D48110P	A06		YC051-YC052	
1301	20	X1	EN		67-8	74-11-11	D39925	3			D48110P	A06		YC053-YL999, YR301-YR328	
1301	20	X1	EN		57-9	74-11-11	D39925	3			D48110P	A06		YN231-YN501	
1301Z			EN		0-0	74-11-11	D39925	S/R			D48110P	PERG	1F	ALL	
1302	20	X1	EP		67-10	73-22-11	D39925	5			D48110P	A05		YC051-YC052	
1302	20	X1	EP		67-8	73-22-11	D39925	5			D48110P	A05		YC053-YL999, YR301-YR328	
1302	20	X1	EP		57-9	73-22-11	D39925	5			D48110P	A05		YN231-YN501	
1302Z			EP		0-0	73-22-11	D39925	S/R			D48110P	PERG	1F	ALL	
2601B	20	PB	SA		40-2	SPARE	D39925	10			D40734J	1		YC051-YL999, YR301-YR328	
2601B	20	PB	SA		30-2	SPARE	D39925	10			D40734J	1		YN231-YN501	
2601R	20	PB	SA		0-0	SPARE	D39925	2			D40734J	2		ALL	
2602B	20	PB	SB		40-2	SPARE	D39925	11			D40734J	3		YC051-YL999, YR301-YR328	
2602B	20	PB	SB		30-2	SPARE	D39925	11			D40734J	3		YN231-YN501	
2602R	20	PB	SB		0-0	SPARE	D39925	24			D40734J	4		ALL	

WIRE LIST

D280A108

91-21-11

Section W5170

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5170	286A5170				LEFT WING/BODY PRESS SEAL TO E/E BAY (continued)										
2603B	20	PB	SC		40-2	SPARE	D39925		15		D40734J		5		YC051-YL999, YR301-YR328
2603B	20	PB	SC		30-2	SPARE	D39925		15		D40734J		5		YN231-YN501
2603R	20	PB	SC		0-0	SPARE	D39925		16		D40734J		6		ALL
2604R	20	RJ	SD		40-2	77-31-11	D39925		17		D40734J		7		YC051-YD153
2604R	20	RJ	SD		40-2	77-31-11	D39925		6		D40734J		7		YD154-YL999, YR301-YR328
2604R	20	RJ	SD		30-2	77-31-11	D39925		6		D40734J		7		YN231-YN501
2604W	20	RJ	SD		0-0	77-31-11	D39925		18		D40734J		8		YC051-YD153
2604W	20	RJ	SD		0-0	77-31-11	D39925		1		D40734J		8		YD154-YR328
2604Z			SD		0-0	77-31-11	D39925		7		D40734J		9		ALL
2605B	24	Y2	SE		40-2	77-12-11	D39925		39		D40734J		16		YC051-YL999, YR301-YR328
2605B	24	Y2	SE		30-2	77-12-11	D39925		39		D40734J		16		YN231-YN501
2605R	24	Y2	SE		0-0	77-12-11	D39925		19		D40734J		15		ALL
2605Z			SE		0-0	77-12-11	D39925		S/R		D40734J		S/R		ALL
2608B	22	PB	SH		67-10	30-21-11	D39925		22		D48110P		A03		YC051-YC052
2608B	22	PB	SH		67-8	30-21-11	D39925		22		D48110P		A03		YC053-YL999, YR301-YR328
2608B	22	PB	SH		57-9	30-21-11	D39925		22		D48110P		A03		YN231-YN501
2608R	22	PB	SH		0-0	30-21-11	D39925		21		D48110P		A02		ALL
3601B	24	Y3	A4		40-2	79-31-11	D39925		36		D40734J		12		YC051-YL999, YR301-YR328
3601B	24	Y3	A4		30-2	79-31-11	D39925		36		D40734J		12		YN231-YN501
3601R	24	Y3	A4		0-0	79-31-11	D39925		35		D40734J		13		ALL
3601Y	24	Y3	A4		0-0	79-31-11	D39925		37		D40734J		14		ALL
3601Z			A4		0-0	79-31-11	D39925		S/R		D40734J		S/R		ALL
6001R	20	PH			40-2	26-11-11	D39925		28		D40734J		23		YC051-YL999, YR301-YR328
6001R	20	PH			30-2	26-11-11	D39925		28		D40734J		23		YN231-YN501
6002R	20	PH			40-2	26-11-11	D39925		29		D40734J		22		YC051-YL999, YR301-YR328
6002R	20	PH			30-2	26-11-11	D39925		29		D40734J		22		YN231-YN501
6005	22	PA			67-10	30-21-11	D39925		23		D48110P		A04		YC051-YC052
6005	22	PA			67-8	30-21-11	D39925		23		D48110P		A04		YC053-YL999, YR301-YR328
6005	22	PA			57-9	30-21-11	D39925		23		D48110P		A04		YN231-YN501
6006	20	PA			67-10	30-21-11	D39925		38		D48110P		A01		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W5170

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To						
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W5170	286A5170				LEFT WING/BODY PRESS SEAL TO E/E BAY (continued)												
6006	20		PA		67-8		30-21-11	D39925			38		D48110P	A01			YC053-YL999, YR301-YR328
6006	20		PA		57-9		30-21-11	D39925			38		D48110P	A01			YN231-YN501
6008	20		PA		54-4		28-21-11	D39925			30		TB0261Y	B005	1A		YC051-YC052
6008	20		PA		56-7		28-21-11	D39925			30		TB0261Y	B005	1A		YC053-YL999, YR301-YR328
6008	20		PA		46-0		28-21-11	D39925			30		TB0261Y	B005	1A		YN231-YN501
6009	20		CQ		54-4		28-21-11	D39925			31		TB0261Y	A011	1A		YC051-YC052
6009	20		CQ		56-7		28-21-11	D39925			31		TB0261Y	A011	1A		YC053-YL999, YR301-YR328
6009	20		CQ		46-1		28-21-11	D39925			31		TB0261Y	A011	1A		YN231-YN501
6010	20		PA		54-4		28-21-11	D39925			32		TB0261X	B004	1A		YC051-YC052
6010	20		PA		56-7		28-21-11	D39925			32		TB0261X	B004	1A		YC053-YL999, YR301-YR328
6010	20		PA		45-11		28-21-11	D39925			32		TB0261X	B004	1A		YN231-YN501
6011	20		CQ		19-11		28-21-11	TB0261Y		A011	1A		SP00656			S	YC051-YC052
6011	20		CQ		21-4		28-21-11	TB0261Y		A011	1A		SP00656			S	YC053-YR328
6501	24		PK		40-2		31-62-14	D40734J			17		D39925		8		YC051-YL999, YR301-YR328
6501	24		PK		30-2		31-62-14	D40734J			17		D39925		8		YN231-YN501
6502	24		PK		40-2		31-62-14	D39925			33		D40734J		24		YC051-YL999, YR301-YR328
6502	24		PK		30-2		31-62-14	D39925			33		D40734J		24		YN231-YN501
W5172	286A5172				LEFT WING/BODY PRESS SEAL TO E/E BAY												
0009	18		PA		1-0		78-32-51	D39917			1		GD01230	DC..	1		YC051-YC054
0009	18		PA		6-7		78-32-51	D39917			1		GD01230	DC..	1		YC055-YL999, YR301-YR328
0009	18		PA		7-7		78-32-51	D39917			1		GD01230	DC..	1		YN231-YN501
0010	18		PA		1-0		78-32-51	D39917			5		GD01230	DC..	1		YC051-YC054
0010	18		PA		6-7		78-32-51	D39917			5		GD01230	DC..	1		YC055-YL999, YR301-YR328
0010	18		PA		7-7		78-32-51	D39917			5		GD01230	DC..	1		YN231-YN501
0011	20		PA		1-0		78-36-11	D39917			8		GD01230	DC..	1		YC051-YC054
0011	20		PA		6-7		78-36-11	D39917			8		GD01230	DC..	1		YC055-YL999, YR301-YR328
0011	20		PA		7-7		78-36-11	D39917			8		GD01230	DC..	1		YN231-YN501
0012	20		PA		1-0		73-21-12	D39917			9		GD01230	DC..	1		YC051-YC054

WIRE LIST

D280A108

91-21-11

Section W5170

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W5172	286A5172				LEFT WING/BODY PRESS SEAL TO E/E BAY (continued)												
0012	20		PA		6-7	73-21-12		D39917		9		GD01230	DC..	1		YC055-YL999, YR301-YR328	
0012	20		PA		7-7	73-21-12		D39917		9		GD01230	DC..	1		YN231-YN501	
0013	20		PA		1-0	78-36-11		D39917		18		GD01230	DC..	1		YC051-YC054	
0013	20		PA		6-7	78-36-11		D39917		18		GD01230	DC..	1		YC055-YL999, YR301-YR328	
0013	20		PA		7-7	78-36-11		D39917		18		GD01230	DC..	1		YN231-YN501	
0014	20		PA		1-0	78-35-11		D39917		36		GD01230	DC..	1		YC051-YC054	
0014	20		PA		6-7	78-35-11		D39917		36		GD01230	DC..	1		YC055-YL999, YR301-YR328	
0014	20		PA		7-7	78-35-11		D39917		36		GD01230	DC..	1		YN231-YN501	
1301	24		Y1	EN	66-10	73-21-12		D39917		21		D48136P	A03			YC051-YC054	
1301	24		Y1	EN	67-4	73-21-12		D39917		21		D48136P	A03			YC055-YL999, YR301-YR328	
1301	24		Y1	EN	57-2	73-21-12		D39917		21		D48136P	A03			YN231-YN501	
1301Z				EN	0-0	73-21-12		D39917		S/R		D48136P	PERG	1F		ALL	
2601B	18		X2	SA	67-5	78-32-51		D39917		16		TB1808V	B007	1		YC051-YC054	
2601B	18		X2	SA	67-10	78-32-51		D39917		16		TB1808V	B007	1		YC055-YL999, YR301-YR328	
2601B	18		X2	SA	57-7	78-32-51		D39917		16		TB1808V	B007	1		YN231-YN501	
2601R	18		X2	SA	0-0	78-32-51		D39917		6		TB1808V	A007	1		ALL	
2601Z				SA	0-0	78-32-51		D39917		S/R		GB01808	ST..	1A		ALL	
2602B	18		X2	SB	67-5	78-32-51		D39917		7		TB1808V	B005	1		YC051-YC054	
2602B	18		X2	SB	67-10	78-32-51		D39917		7		TB1808V	B005	1		YC055-YL999, YR301-YR328	
2602B	18		X2	SB	57-7	78-32-51		D39917		7		TB1808V	B005	1		YN231-YN501	
2602R	18		X2	SB	0-0	78-32-51		D39917		17		TB1808V	A005	1		ALL	
2602Z				SB	0-0	78-32-51		D39917		S/R		GB01808	ST..	1A		ALL	
2604B	20		X2	SD	39-3	SPARE		D39917		12		D40736J		1		YC051-YC054	
2604B	20		X2	SD	39-8	SPARE		D39917		12		D40736J		1		YC055-YL999, YR301-YR328	
2604B	20		X2	SD	29-4	SPARE		D39917		12		D40736J		1		YN231-YN501	
2604R	20		X2	SD	0-0	SPARE		D39917		3		D40736J		2		ALL	
2604Z				SD	0-0	SPARE		D39917		S/R		D40736J	S/R			ALL	
2605B	20		X2	SE	39-3	SPARE		D39917		14		D40736J		4		YC051-YC054	
2605B	20		X2	SE	39-8	SPARE		D39917		14		D40736J		4		YC055-YL999, YR301-YR328	
2605B	20		X2	SE	29-4	SPARE		D39917		14		D40736J		4		YN231-YN501	
2605R	20		X2	SE	0-0	SPARE		D39917		32		D40736J		5		ALL	

WIRE LIST

D280A108

91-21-11

Section W5170

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To			Effectivity				
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type		Splice	Equip	Term	Type
W5172	286A5172			LEFT WING/BODY PRESS SEAL TO E/E BAY (continued)											
2605Z				SE	0-0	SPARE	D39917		S/R		D40736J		S/R		ALL
2606B		22	PB	SF	39-3	78-36-11	D39917		19		D40736J		7		YC051-YC054
2606B		22	PB	SF	39-8	78-36-11	D39917		19		D40736J		7		YC055-YL999, YR301-YR328
2606B		22	PB	SF	29-4	78-36-11	D39917		19		D40736J		7		YN231-YN501
2606R		22	PB	SF	0-0	78-36-11	D39917		20		D40736J		8		ALL
2607B		22	PB	SG	39-3	78-36-11	D39917		38		D40736J		9		YC051-YC054
2607B		22	PB	SG	39-8	78-36-11	D39917		38		D40736J		9		YC055-YL999, YR301-YR328
2607B		22	PB	SG	29-4	78-36-11	D39917		38		D40736J		9		YN231-YN501
2607R		22	PB	SG	0-0	78-36-11	D39917		39		D40736J		10		ALL
2608B		24	Y2	SH	39-3	73-24-11	D39917		34		D40736J		11		YC051-YC054
2608B		24	Y2	SH	39-8	73-24-11	D39917		34		D40736J		11		YC055-YL999, YR301-YR328
2608B		24	Y2	SH	29-4	73-24-11	D39917		34		D40736J		11		YN231-YN501
2608R		24	Y2	SH	0-0	73-24-11	D39917		33		D40736J		12		ALL
2608Z				SH	0-0	73-24-11	D39917		S/R		D40736J		S/R		ALL
2609B		24	Y2	SI	66-10	73-21-11	D39917		23		D48136P		A02		YC051-YC054
2609B		24	Y2	SI	67-4	73-21-11	D39917		23		D48136P		A02		YC055-YL999, YR301-YR328
2609B		24	Y2	SI	57-2	73-21-11	D39917		23		D48136P		A02		YN231-YN501
2609R		24	Y2	SI	0-0	73-21-11	D39917		22		D48136P		A01		ALL
2609Z				SI	0-0	73-21-11	D39917		S/R		D48136P		PERG	1F	ALL
2610B		24	Y2	SJ	53-9	73-21-12	D39917		31		TB0261X		B001	1A	YC051-YC054
2610B		24	Y2	SJ	54-2	73-21-12	D39917		31		TB0261X		B001	1A	YC055-YL999, YR301-YR328
2610B		24	Y2	SJ	43-6	73-21-12	D39917		31		TB0261X		B001	1A	YN231-YN501
2610R		24	Y2	SJ	0-0	73-21-12	D39917		30		TB0261X		A001	1A	ALL
2610Z				SJ	0-0	73-21-12	D39917		S/R		GB00261		ST..	1A	ALL
2611B		20	X2	SK	71-0	73-21-21	D39917		11		D11158		5		YC051-YC054
2611B		20	X2	SK	71-5	73-21-21	D39917		11		D11158		5		YC055-YL999, YR301-YR328
2611B		20	X2	SK	60-11	73-21-21	D39917		11		D11158		5		YN231-YN501
2611R		20	X2	SK	0-0	73-21-21	D39917		26		D11158		15		ALL
2611Z				SK	0-0	73-21-21	D39917		S/R		D11158		S/R		ALL
2612B		20	X2	SL	71-0	73-21-21	D39917		27		D11158		7		YC051-YC054
2612B		20	X2	SL	71-5	73-21-21	D39917		27		D11158		7		YC055-YL999, YR301-YR328
2612B		20	X2	SL	60-11	73-21-21	D39917		27		D11158		7		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W5170

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To					
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W5172	286A5172				LEFT WING/BODY PRESS SEAL TO E/E BAY (continued)											
2612R	20	X2	SL		0-0	73-21-21	D39917		28			D11158	8			ALL
2612Z			SL		0-0	73-21-21	D39917		S/R			D11158	S/R			ALL
2613B	20	X2	SM		71-0	73-21-21	D39917		25			D11158	2			YC051-YC054
2613B	20	X2	SM		71-5	73-21-21	D39917		25			D11158	2			YC055-YL999, YR301-YR328
2613B	20	X2	SM		60-11	73-21-21	D39917		25			D11158	2			YN231-YN501
2613R	20	X2	SM		0-0	73-21-21	D39917		24			D11158	10			ALL
2613Z			SM		0-0	73-21-21	D39917		S/R			D11158	S/R			ALL
2614B	24	Y2	SN		39-3	73-24-12	D39917		35			D40736J	13			YC051-YC054
2614B	24	Y2	SN		39-8	73-24-12	D39917		35			D40736J	13			YC055-YL999, YR301-YR328
2614B	24	Y2	SN		29-4	73-24-12	D39917		35			D40736J	13			YN231-YN501
2614R	24	Y2	SN		0-0	73-24-12	D39917		15			D40736J	14			ALL
2614Z			SN		0-0	73-24-12	D39917		S/R			D40736J	S/R			ALL
2617B	24	Y2	SR		53-9	74-31-11	D39917		29			TB0261Y	B007	1A		YC051-YC054
2617B	24	Y2	SR		54-2	74-31-11	D39917		29			TB0261Y	B007	1A		YC055-YL999, YR301-YR328
2617B	24	Y2	SR		43-6	74-31-11	D39917		29			TB0261Y	B007	1A		YN231-YN501
2617R	24	Y2	SR		0-0	74-31-11	D39917		13			TB0261Y	A007	1A		ALL
2617Z			SR		0-0	74-31-11	D39917		S/R			GB00261	ST..	1A		ALL
6001	20	PA			66-10	78-35-11	D39917		37			D48136P	A04			YC051-YC054
6001	20	PA			67-4	78-35-11	D39917		37			D48136P	A04			YC055-YL999, YR301-YR328
6001	20	PA			57-2	78-35-11	D39917		37			D48136P	A04			YN231-YN501
6002	20	PA			3-6	73-21-21	D11158		13			GD00815	ST..	1A		ALL

WIRE LIST

D280A108

91-21-11
Section W5170
Page 6 End
Nov 12/2012

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To					
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W5181	286A5181			ATC BOTTOM ANT E1 RACK (S943) TO STA 355 (M44)											
001CO				AA	0-0	34-53-31	D00099	= C1			D02707	= C1			ALL
001CX		OG		AA	6-6	34-53-31	D00099	= A1			D02707	= A1			ALL
W5182	286A5182			ISPC TO P18(EE-BAY TO PC POWER OUTLET(P18)											
0002	20		PA		30-0	SPARE	D13908	CAP	Y		D13906	CAP	Y		YL951-YL999, YN232-YR328
0003	20		PA		30-0	25-29-11	D13908		3		D13906		3		YL951-YL999, YN232-YR328
0004	20		PA		30-0	SPARE	D13908	CAP	Y		D13906	CAP	Y		YL951-YL999, YN232-YR328
0006	20		PA		30-0	25-29-11	D13908		6		D13906		6		YL951-YL999, YN232-YR328
0007	20		PA		30-0	25-29-11	D13908		7		D13906		7		YL951-YL999, YN232-YR328
0008	20		PA		30-0	25-29-11	D13908		8		D13906		8		YL951-YL999, YN232-YR328
0009	20		PA		30-0	25-29-11	D13908		9		D13906		9		YL951-YL999, YN232-YR328
2001B	20		PB	AA	30-0	25-29-11	D13908		5		D13906		5		YL951-YL999, YN232-YR328
2001R	20		PB	AA	0-0	25-29-11	D13908		1		D13906		1		YL951-YL999, YN232-YR328
YAAA					0-0	25-29-11	D13906	DED			D13908	PERB			YL951-YL999, YN232-YR328
W5183	286A5183			DME 1 E1-2 TO DME LEFT BOTTOM ANTENNA											
001CO				AA	0-0	34-55-11	D41215J	= C1			D00093	= C1			ALL
001CX		OH		AA	46-10	34-55-11	D41215J	= A1			D00093	= A1			YC051-YL999, YR301-YR328
001CX		OH		AA	37-0	34-55-11	D41215J	= A1			D00093	= A1			YN231-YN501
W5185	286A5185			DME 2 E1-5 TO DME RIGHT BOTTOM ANTENNA											
001CO				AA	0-0	34-55-21	D41515J	= C1			D00095	= C1			ALL
001CX		OH		AA	48-7	34-55-21	D41515J	= A1			D00095	= A1			YC051-YC064
001CX		OH		AA	48-9	34-55-21	D41515J	= A1			D00095	= A1			YC065-YL999, YR301-YR328
001CX		OH		AA	38-11	34-55-21	D41515J	= A1			D00095	= A1			YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W5180

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5189	286A5189			E4-1 AUDIO NO. 1											
0001	22		PA		15-11	SPARE	D04195P		42		D48389P	A01			YC051-YC052
0001	22		PA		15-3	SPARE	D04195P		42		D48389P	A01			YC053-YC055
0001	22		PA		14-10	SPARE	D04195P		42		D48389P	A01			YC056-YD170
0002	22		PA		15-11	SPARE	D04195P		43		D48389P	B01			YC051-YC052
0002	22		PA		15-3	SPARE	D04195P		43		D48389P	B01			YC053-YC055
0002	22		PA		14-10	SPARE	D04195P		43		D48389P	B01			YC056-YD170
0003	22		PA		24-4	23-31-02	D08123P	A01			D04195P	3			YC051-YC055
0003	22		PA		24-10	23-31-02	D08123P	A01			D04195P	3			YC056-YR328
0004	24		PK		24-4	23-31-02	D08123P	B01			D04195P	4			YC051-YC055
0004	24		PK		24-10	23-31-02	D08123P	B01			D04195P	4			YC056-YR328
0005	24		PK		24-4	23-31-04	D08123P	A02			D04195P	15			YC051-YC055
0005	24		PK		24-10	23-31-04	D08123P	A02			D04195P	15			YC056-YR328
0006	24		PK		24-4	23-31-04	D08123P	B02			D04195P	18			YC051-YC055
0006	24		PK		24-10	23-31-04	D08123P	B02			D04195P	18			YC056-YR328
0007	24		PK		24-4	23-31-04	D08123P	A03			D04195P	19			YC051-YC055
0007	24		PK		24-10	23-31-04	D08123P	A03			D04195P	19			YC056-YR328
0008	24		PK		24-4	23-31-04	D08123P	B03			D04195P	20			YC051-YC055
0008	24		PK		24-10	23-31-04	D08123P	B03			D04195P	20			YC056-YR328
0009	24		PK		15-11	23-34-01	D04195P	44			D48389P	A02			YC051-YC052
0009	24		PK		15-3	23-34-01	D04195P	44			D48389P	A02			YC053-YC055
0009	24		PK		14-10	23-34-01	D04195P	44			D48389P	A02			YC056-YD170
0010	24		PK		15-11	23-34-01	D04195P	45			D48389P	B02			YC051-YC052
0010	24		PK		15-3	23-34-01	D04195P	45			D48389P	B02			YC053-YC055
0010	24		PK		14-10	23-34-01	D04195P	45			D48389P	B02			YC056-YD170
0011	22		CQ		24-6	23-42-12	D04287P	A01			D04195P	24			YC051-YC055
0011	22		CQ		25-1	23-42-12	D04287P	A01			D04195P	24			YC056-YN260, YR315-YR328
0012	22		CQ		24-6	23-12-11	D04287P	B01			D04195P	34			YC051-YC055
0012	22		CQ		25-1	23-12-11	D04287P	B01			D04195P	34			YC056-YD170
0012	22		PA		25-1	23-12-11	D04287P	B01			D04195P	34			YL951-YR328
0013	22		CQ		24-6	23-12-11	D04287P	A02			D04195P	40			YC051-YC055
0013	22		CQ		25-1	23-12-11	D04287P	A02			D04195P	40			YC056-YD170
0013	22		PA		25-1	23-12-11	D04287P	A02			D04195P	40			YL951-YR328
0014	24		PK		15-11	23-34-01	D04195P	46			D48389P	A03			YC051-YC052
0014	24		PK		15-3	23-34-01	D04195P	46			D48389P	A03			YC053-YC055
0014	24		PK		14-10	23-34-01	D04195P	46			D48389P	A03			YC056-YD170
0015	20		CQ		31-5	23-34-01	D40702P	13			D48389P	A04			YC051-YC052
0015	20		CQ		30-9	23-34-01	D40702P	13			D48389P	A04			YC053
0017	22		PA		20-10	SPARE	D43315P	B10			D48389P	B05			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W5189

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W5189	286A5189				E4-1 AUDIO NO. 1 (continued)											
0017	22	PA		20-3	SPARE	D43315P		B10			D48389P	B05		YC053-YC055		
0017	22	PA		20-4	SPARE	D43315P		B10			D48389P	B05		YC056-YD157		
0018	22	PA		9-9	23-27-11	D08123P		A17			D43315P	A01		YC051-YC055		
0018	22	PA		10-7	23-27-11	D08123P		A17			D43315P	A01		YC056-YD157		
0018	22	PA		10-7	SPARE	D08123P		A17			D43315P	A01		YD158-YD170		
0019	22	PA		9-9	23-27-11	D08123P		B17			D43315P	A02		YC051-YC055		
0019	22	PA		10-7	23-27-11	D08123P		B17			D43315P	A02		YC056-YD157		
0019	22	PA		10-7	SPARE	D08123P		B17			D43315P	A02		YD158-YD170		
0020	22	PA		9-9	23-27-11	D08123P		A18			D43315P	A03		YC051-YC055		
0020	22	PA		10-7	23-27-11	D08123P		A18			D43315P	A03		YC056-YD157		
0020	22	PA		10-7	SPARE	D08123P		A18			D43315P	A03		YD158-YD170		
0021	24	B6		19-1	31-31-17	D08123P		A10			D08189P	B07		YC051-YC052		
0021	24	B6		19-5	31-31-17	D08123P		A10			D08189P	B07		YC053-YC055		
0021	24	B6		19-11	31-31-17	D08123P		A10			D08189P	B07		YC056-YD170		
0021	24	PK		119-0	31-31-17	D08123P		A10			D40117P	B07		YL951-YL999		
0021	24	PK		98-10	31-31-17	D08123P		A10			D40117P	B07		YN231-YN501		
0021	24	PK		118-8	31-31-17	D08123P		A10			D40117P	B07		YR301-YR328		
0022	22	CQ		19-1	23-29-11	D08123P		A13			D08189P	A07		YC051-YC052		
0022	22	CQ		19-5	23-29-11	D08123P		A13			D08189P	A07		YC053-YC055		
0022	22	CQ		19-11	23-29-11	D08123P		A13			D08189P	A07		YC056-YD157		
0022	22	PA		19-11	23-11-11	D08123P		B15			D08189P	A10		YD158-YD170		
0022	22	PA		119-0	23-11-11	D08123P		B15			D40117P	A10		YL951-YL999		
0022	22	PA		98-10	23-11-11	D08123P		B15			D40117P	A10		YN231-YN501		
0022	22	PA		118-8	23-11-11	D08123P		B15			D40117P	A10		YR301-YR328		
0023	22	CQ		9-9	23-12-31	D43315P		B01			D08123P	B18		YC051-YC055		
0023	22	CQ		10-7	23-12-31	D43315P		B01			D08123P	B18		YC056-YD157		
0024	22	CQ		9-9	23-12-31	D43315P		B02			D08123P	B20		YC051-YC055		
0024	22	CQ		10-7	23-12-31	D43315P		B02			D08123P	B20		YC056-YD157		
0026	20	CQ		31-5	23-34-01	D40702P		21			D48389P	A06		YC051-YC052		
0026	20	CQ		30-9	23-34-01	D40702P		21			D48389P	A06		YC053		
0027	24	PK		15-11	23-34-01	D04195P		50			D48389P	A09		YC051-YC052		
0027	24	PK		15-3	23-34-01	D04195P		50			D48389P	A09		YC053		
0027	24	PK		15-3	23-34-01	D04195P		50			D48389P	B03		YC054-YC055		
0027	24	PK		14-10	23-34-01	D04195P		50			D48389P	B03		YC056-YD170		
0037	24	PK		13-2	23-11-16	D04195P		55			D08189P	B10		YD158-YD170		
0055	22	PA		114-11	SPARE	D04271P		A03			D40117P	B02		YL951-YL999		
0055	22	PA		94-9	23-11-16	D04271P		A03			D40117P	B02		YN231-YN260		
0055	22	PA		94-9	MULTI	D04271P		A03			D40117P	B02		YN501		
0055	22	PA		114-7	SPARE	D04271P		A03			D40117P	B02		YR301-YR328		

WIRE LIST

D280A108

91-21-11

Section W5180

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5189	286A5189			E4-1 AUDIO NO. 1 (continued)											
0073	22		PA		24-10	SPARE	D08123P	B16			D04195P	55			YL951-YN260, YR301-YR328
0073	22		PA		24-10	MULTI	D08123P	B16			D04195P	55			YN501
2002B	24		PL	AC	24-4	23-31-02	D08123P	B04			D04195P	14			YC051-YC055
2002B	24		PL	AC	24-10	23-31-02	D08123P	B04			D04195P	14			YC056-YR328
2002R	24		PL	AC	0-0	23-31-02	D08123P	A04			D04195P	13			ALL
2003B	24		PL	AD	24-4	23-31-02	D08123P	B05			D04195P	6			YC051-YC055
2003B	24		PL	AD	24-10	23-31-02	D08123P	B05			D04195P	6			YC056-YR328
2003R	24		PL	AD	0-0	23-31-02	D08123P	A05			D04195P	5			ALL
2004B	24		PL	AE	24-4	23-31-02	D08123P	B06			D04195P	8			YC051-YC055
2004B	24		PL	AE	24-10	23-31-02	D08123P	B06			D04195P	8			YC056-YR328
2004R	24		PL	AE	0-0	23-31-02	D08123P	A06			D04195P	7			ALL
2005B	24		PL	AF	24-4	23-31-02	D08123P	B07			D04195P	10			YC051-YC055
2005B	24		PL	AF	24-10	23-31-02	D08123P	B07			D04195P	10			YC056-YR328
2005R	24		PL	AF	0-0	23-31-02	D08123P	A07			D04195P	9			ALL
2006B	22		PB	AG	24-4	23-31-02	D08123P	B08			D04195P	12			YC051-YC055
2006B	22		PB	AG	24-10	23-31-02	D08123P	B08			D04195P	12			YC056-YR328
2006R	22		PB	AG	0-0	23-31-02	D08123P	A08			D04195P	11			ALL
2007B	22		PB	AH	24-4	23-31-04	D08123P	B09			D04195P	17			YC051-YC055
2007B	22		PB	AH	24-10	23-31-04	D08123P	B09			D04195P	17			YC056-YR328
2007R	22		PB	AH	0-0	23-31-04	D08123P	A09			D04195P	16			ALL
2501B	24		M5	AB	29-1	34-55-11	D04287P	B04			D04269J	11			YC051-YC055
2501B	24		M5	AB	29-8	34-55-11	D04287P	B04			D04269J	11			YC056-YR328
2501R	24		M5	AB	0-0	34-55-11	D04287P	A04			D04269J	10			ALL
2501ZI				AB	0-0	34-55-11	D04287P	B05			D04269J	12			ALL
2501ZO				AB	0-0	34-55-11	D04287P	PERG	1F		D04269J	S/R			ALL
2502B	24		M5	AI	7-2	34-57-11	D04287P	B06			D04271P	B01			YC051-YC055
2502B	24		M5	AI	8-1	34-57-11	D04287P	B06			D04271P	B01			YC056-YR328
2502R	24		M5	AI	0-0	34-57-11	D04287P	A06			D04271P	A01			ALL
2502ZI				AI	0-0	34-57-11	D04287P	A05			D04271P	A02			ALL
2502ZO				AI	0-0	34-57-11	D04287P	PERG	1F		D04271P	PERG	1F		ALL
2503B	24		M5	AJ	24-6	23-22-11	D04287P	B07			D04195P	22			YC051-YC055
2503B	24		M5	AJ	25-1	23-22-11	D04287P	B07			D04195P	22			YC056-YR328
2503R	24		M5	AJ	0-0	23-22-11	D04287P	A07			D04195P	21			ALL
2503ZI				AJ	0-0	23-22-11	D04287P	B02			D04195P	23			ALL
2503ZO				AJ	0-0	23-22-11	D04287P	PERG	1F		D04195P	41			ALL
2505B	24		M5	AM	29-1	34-31-11	D04287P	B08			D04269J	2			YC051-YC055
2505B	24		M5	AM	29-8	34-31-11	D04287P	B08			D04269J	2			YC056-YR328
2505R	24		M5	AM	0-0	34-31-11	D04287P	A08			D04269J	1			ALL

WIRE LIST

D280A108

91-21-11

Section W5180

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5189		286A5189			E4-1 AUDIO NO. 1 (continued)											
2505ZI					AM	0-0	34-31-11	D04287P	B09			D04269J	3			ALL
2505ZO					AM	0-0	34-31-11	D04287P	PERG	1F		D04269J	S/R			ALL
2506B	24	M5			AN	29-1	34-32-11	D04287P	B10			D04269J	5			YC051-YC055
2506B	24	M5			AN	29-8	34-32-11	D04287P	B10			D04269J	5			YC056-YR328
2506R	24	M5			AN	0-0	34-32-11	D04287P	A10			D04269J	4			ALL
2506ZI					AN	0-0	34-32-11	D04287P	A09			D04269J	6			ALL
2506ZO					AN	0-0	34-32-11	D04287P	PERG	1F		D04269J	S/R			ALL
2507B	24	M5			AP	29-1	34-51-11	D04287P	B11			D04269J	8			YC051-YC055
2507B	24	M5			AP	29-8	34-51-11	D04287P	B11			D04269J	8			YC056-YR328
2507R	24	M5			AP	0-0	34-51-11	D04287P	A11			D04269J	7			ALL
2507ZI					AP	0-0	34-51-11	D04287P	B12			D04269J	9			ALL
2507ZO					AP	0-0	34-51-11	D04287P	PERG	1F		D04269J	S/R			ALL
2508B	24	M5			AQ	24-6	23-12-11	D04287P	B13			D04195P	32			YC051-YC055
2508B	24	M5			AQ	25-1	23-12-11	D04287P	B13			D04195P	32			YC056-YR328
2508R	24	M5			AQ	0-0	23-12-11	D04287P	A13			D04195P	31			ALL
2508ZI					AQ	0-0	23-12-11	D04287P	A12			D04195P	33			ALL
2508ZO					AQ	0-0	23-12-11	D04287P	PERG	1F		D04195P	39			ALL
2509B	24	M5			AR	24-6	23-12-11	D04287P	B14			D04195P	29			YC051-YC055
2509B	24	M5			AR	25-1	23-12-11	D04287P	B14			D04195P	29			YC056-YR328
2509R	24	M5			AR	0-0	23-12-11	D04287P	A14			D04195P	28			ALL
2509ZI					AR	0-0	23-12-11	D04287P	B15			D04195P	30			ALL
2509ZO					AR	0-0	23-12-11	D04287P	PERG	1F		D04195P	27			ALL
2510B	24	M5			AL	10-0	23-22-11	D04287P	B19			D43315P	B07			YC051-YC055
2510B	24	M5			AL	10-10	23-22-11	D04287P	B19			D43315P	B07			YC056-YD170
2510R	24	M5			AL	0-0	23-22-11	D04287P	A19			D43315P	A07			YC051-YD170
2510ZI					AL	0-0	23-22-11	D04287P	B20			D43315P	A06			YC051-YD170
2510ZO					AL	0-0	23-22-11	D04287P	PERG	1F		D43315P	PERG	1F		YC051-YD170
2511B	24	M5			AA	7-2	34-49-11	D04287P	B03			D04271P	B04			YC051-YC055
2511B	24	M5			AA	8-1	34-49-11	D04287P	B03			D04271P	B04			YC056-YR328
2511R	24	M5			AA	0-0	34-49-11	D04287P	A03			D04271P	A04			ALL
2511ZI					AA	0-0	34-49-11	D04287P	B18			D04271P	A05			ALL
2511ZO					AA	0-0	34-49-11	D04287P	PERG	1F		D04271P	PERG	1F		ALL
2512B	24	M5			AK	19-1	23-11-11	D08123P	A19			D08189P	A01			YC051-YC052
2512B	24	M5			AK	19-5	23-11-11	D08123P	A19			D08189P	A01			YC053-YC055
2512B	24	M5			AK	19-11	23-11-11	D08123P	A19			D08189P	A01			YC056-YD157
2512B	24	M5			AK	19-11	23-11-11	D08123P	B13			D08189P	B01			YD158-YD170
2512B	24	M5			BS	119-0	23-11-11	D08123P	B13			D40117P	B01			YL951-YL999
2512B	24	M5			BS	98-10	23-11-11	D08123P	B13			D40117P	B01			YN231-YN501
2512B	24	M5			BS	118-8	23-11-11	D08123P	B13			D40117P	B01			YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W5180

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5189	286A5189			E4-1 AUDIO NO. 1 (continued)											
2512R	24	M5	AK		0-0	23-11-11	D08123P	B19			D08189P	B01			YC051-YD157
2512R	24	M5	AK		0-0	23-11-11	D08123P	A13			D08189P	A01			YD158-YD170
2512R	24	M5	BS		0-0	23-11-11	D08123P	A13			D40117P	A01			YL951-YR328
2512ZI			AK		0-0	23-11-11	D08123P	A20			D08189P	A02			YC051-YD157
2512ZI			AK		0-0	23-11-11	D08123P	B12			D08189P	A02			YD158-YD170
2512ZI			BS		0-0	23-11-11	D08123P	B12			D40117P	A02			YL951-YR328
2512ZO			AK		0-0	23-11-11	D08123P	PERG	1F		D08189P	PERG	1F		YC051-YD170
2512ZO			BS		0-0	23-11-11	D08123P	PERG	1F		D40117P	PERG	1F		YL951-YR328
2513B	24	M5	AU		19-11	23-11-11	D08123P	B11			D08189P	B06			YD158-YD170
2513B	24	M5	BH		119-0	23-11-11	D08123P	B11			D40117P	B06			YL951-YL999
2513B	24	M5	BH		98-10	23-11-11	D08123P	B11			D40117P	B06			YN231-YN501
2513B	24	M5	BH		118-8	23-11-11	D08123P	B11			D40117P	B06			YR301-YR328
2513R	24	M5	AU		0-0	23-11-11	D08123P	A11			D08189P	A06			YD158-YD170
2513R	24	M5	BH		0-0	23-11-11	D08123P	A11			D40117P	A06			YL951-YR328
2513ZI			AU		0-0	23-11-11	D08123P	B10			D08189P	A07			YD158-YD170
2513ZI			BH		0-0	23-11-11	D08123P	B10			D40117P	A07			YL951-YR328
2513ZO			AU		0-0	23-11-11	D08123P	PERG	1F		D08189P	PERG	1F		YD158-YD170
2513ZO			BH		0-0	23-11-11	D08123P	PERG	1F		D40117P	PERG	1F		YL951-YR328
2514B	24	Y2	AT		15-11	23-34-01	D04195P	48			D48389P	B07			YC051-YC052
2514B	24	Y2	AT		15-3	23-34-01	D04195P	48			D48389P	B07			YC053-YC055
2514B	24	Y2	AT		14-10	23-34-01	D04195P	48			D48389P	B07			YC056-YD170
2514R	24	Y2	AT		0-0	23-34-01	D04195P	47			D48389P	A07			YC051-YD170
2514Z			AT		0-0	23-34-01	D04195P	49			D48389P	A10			YC051-YD170
2515B	24	M5	AV		19-1	23-29-11	D08123P	A14			D08189P	A05			YC051-YC052
2515B	24	M5	AV		19-5	23-29-11	D08123P	A14			D08189P	A05			YC053-YC055
2515B	24	M5	AV		19-11	23-29-11	D08123P	A14			D08189P	A05			YC056-YD157
2515R	24	M5	AV		0-0	23-29-11	D08123P	B14			D08189P	B05			YC051-YD157
2515ZI			AV		0-0	23-29-11	D08123P	B15			D08189P	A06			YC051-YD157
2515ZO			AV		0-0	23-29-11	D08123P	PERG	1F		D08189P	PERG	1F		YC051-YD157
2516B	24	M5	AW		9-9	23-12-31	D43315P	B04			D08123P	B11			YC051-YC055
2516B	24	M5	AW		10-7	23-12-31	D43315P	B04			D08123P	B11			YC056-YD157
2516R	24	M5	AW		0-0	23-12-31	D43315P	A04			D08123P	A11			YC051-YD157
2516ZI			AW		0-0	23-12-31	D43315P	B03			D08123P	B10			YC051-YD157
2516ZO			AW		0-0	23-12-31	D43315P	PERG	1F		D08123P	PERG	1F		YC051-YD157
2517B	24	M5	AX		9-9	23-12-31	D43315P	B05			D08123P	B12			YC051-YC055
2517B	24	M5	AX		10-7	23-12-31	D43315P	B05			D08123P	B12			YC056-YD157
2517R	24	M5	AX		0-0	23-12-31	D43315P	A05			D08123P	A12			YC051-YD157
2517ZI			AX		0-0	23-12-31	D43315P	B06			D08123P	B13			YC051-YD157
2517ZO			AX		0-0	23-12-31	D43315P	PERG	1F		D08123P	PERG	1F		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W5180

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5189	286A5189			E4-1 AUDIO NO. 1 (continued)											
2535B	24	M5	BN		19-1	23-22-11	D08123P	A16			D08189P	A03			YC051-YC052
2535B	24	M5	BN		19-5	23-22-11	D08123P	A16			D08189P	A03			YC053-YC055
2535B	24	M5	BN		19-11	23-22-11	D08123P	A16			D08189P	A03			YC056-YD157
2535B	24	M5	BN		19-11	23-22-11	D08123P	B14			D08189P	B03			YD158-YD170
2535B	24	M5	BN		119-0	23-22-11	D40117P	B03			D08123P	B14			YL951-YL999
2535B	24	M5	BN		98-10	23-22-11	D40117P	B03			D08123P	B14			YN231-YN501
2535B	24	M5	BN		118-8	23-22-11	D40117P	B03			D08123P	B14			YR301-YR328
2535R	24	M5	BN		0-0	23-22-11	D08123P	A15			D08189P	B03			YC051-YD157
2535R	24	M5	BN		0-0	23-22-11	D08123P	A14			D08189P	A03			YD158-YD170
2535R	24	M5	BN		0-0	23-22-11	D40117P	A03			D08123P	A14			YL951-YR328
2535ZI			BN		0-0	23-22-11	D08123P	B16			D08189P	A04			YC051-YD157
2535ZI			BN		0-0	23-22-11	D08123P	A15			D08189P	A04			YD158-YD170
2535ZI			BN		0-0	23-22-11	D40117P	A04			D08123P	A15			YL951-YR328
2535ZO			BN		0-0	23-22-11	D08123P	PERG	1F		D08189P	PERG	1F		YC051-YD170
2535ZO			BN		0-0	23-22-11	D40117P	PERG	1F		D08123P	PERG	1F		YL951-YR328
2538B	24	M5	AY		10-7	SPARE	D08123P	B19			D43315P	B04			YD158-YD170
2538R	24	M5	AY		0-0	SPARE	D08123P	A19			D43315P	A04			YD158-YD170
2538ZI			AY		0-0	SPARE	D08123P	B20			D43315P	B03			YD158-YD170
2538ZO			AY		0-0	SPARE	D08123P	PERG	1F		D43315P	PERG	1F		YD158-YD170
2581B	22	X2	AZ		14-10	23-32-12	D48389P	B04			D04195P	53			YD158-YD170
2581R	22	X2	AZ		0-0	23-32-12	D48389P	A04			D04195P	52			YD158-YD170
2581Z			AZ		0-0	23-32-12	D48389P	B05			D04195P	54			YD158-YD170
3501B	24	Y3	AS		24-6	23-42-12	D04287P	B17			D04195P	36			YC051-YC055
3501B	24	Y3	AS		25-1	23-42-12	D04287P	B17			D04195P	36			YC056-YR328
3501R	24	Y3	AS		0-0	23-42-12	D04287P	A17			D04195P	35			ALL
3501Y	24	Y3	AS		0-0	23-42-12	D04287P	A18			D04195P	37			ALL
3501Z			AS		0-0	23-42-12	D04287P	A16			D04195P	38			ALL

WIRE LIST

D280A108

91-21-11

Section W5180

Page 7 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		Diagram	From				To				
	Wire No.	GA	CO TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5191	286A5191				E4-1 AUDIO NO. 2											
0001	22		CQ		20-2	23-22-11		D04285P	A01			D04273J	7			ALL
0002	22		CQ		29-1	23-12-21		D04285P	B01			D04197J	7			YC051-YC055
0002	22		CQ		29-2	23-12-21		D04285P	B01			D04197J	7			YC056-YD157
0002	22		PA		29-2	23-12-21		D04285P	B01			D04197J	7			YD158-YR328
0003	22		CQ		29-1	23-12-21		D04285P	A02			D04197J	8			YC051-YC055
0003	22		CQ		29-2	23-12-21		D04285P	A02			D04197J	8			YC056-YD157
0003	22		PA		29-2	23-12-21		D04285P	A02			D04197J	8			YD158-YR328
0009	22		PA		28-0	23-11-21		D04285P	A13			D08002P	B02			YD158-YD170
0009	22		PA		105-2	23-11-21		D04285P	A13			D40119P	B02			YL951-YL999, YR301-YR328
0009	22		PA		86-0	23-11-21		D04285P	A13			D40119P	B02			YN231-YN501
0014	22		CQ		7-3	23-12-31		D04289P	B08			D43331P	B17			YD158-YD170
0014	22		PA		7-3	23-12-31		D04289P	B08			D43331P	B17			YL951-YR328
0015	22		PA		7-3	23-12-31		D04289P	B07			D43331P	B19			YD158-YR328
0020	24		PK		28-0	31-31-17		D04285P	B17			D08002P	B04			YD158-YD170
0020	24		PK		105-2	31-31-17		D04285P	B17			D40119P	B04			YL951-YL999, YR301-YR328
0020	24		PK		86-0	31-31-17		D04285P	B17			D40119P	B04			YN231-YN501
0024	22		PA		20-2	23-15-15		D04273J	8			D04285P	A16			YC051-YD157
0024	22		PA		20-2	SPARE		D04273J	8			D04285P	A16			YD158-YD170
0025	20		PA		20-2	23-71-01		D04273J	12			D04285P	B20			ALL
0035	22		PA		7-3	SPARE		D04289P	A06			D43331P	A11			YL951-YR328
0036	24		B6		7-3	SPARE		D04289P	A01			D43331P	A09			YL951-YR328
0037	22		CQ		105-2	SPARE		D04285P	A05			D40119P	B08			YL951-YL999, YR301-YR328
0037	22		CQ		86-0	SPARE		D04285P	A05			D40119P	B08			YN231-YN501
0038	24		G6		7-3	SPARE		D43331P	A05			D04289P	A06			YD158-YD170
0040	24		PK		6-2	31-62-42		D04277P	A06			D04285P	A17			YL951-YR328
2501B	24		M5	AA	29-1	34-55-21		D04285P	B03			D04197J	13			YC051-YC055
2501B	24		M5	AA	29-2	34-55-21		D04285P	B03			D04197J	13			YC056-YR328
2501R	24		M5	AA	0-0	34-55-21		D04285P	A03			D04197J	12			ALL
2501ZI				AA	0-0	34-55-21		D04285P	B02			D04197J	14			ALL
2501ZO				AA	0-0	34-55-21		D04285P	PERG	1F		D04197J	S/R			ALL
2502B	24		M5	AB	6-4	34-57-21		D04285P	B04			D04277P	B01			YC051-YC055
2502B	24		M5	AB	6-2	34-57-21		D04285P	B04			D04277P	B01			YC056-YR328
2502R	24		M5	AB	0-0	34-57-21		D04285P	A04			D04277P	A01			ALL
2502ZI				AB	0-0	34-57-21		D04285P	B05			D04277P	B02			ALL
2502ZO				AB	0-0	34-57-21		D04285P	PERG	1F		D04277P	PERG	1F		ALL
2503B	24		M5	AC	29-1	23-22-11		D04285P	B06			D04197J	10			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5190

Page 1

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W5191	286A5191			E4-1 AUDIO NO. 2 (continued)											
2503B	24	M5	AC	29-2	23-22-11	D04285P	B06				D04197J	10			YC056-YR328
2503R	24	M5	AC	0-0	23-22-11	D04285P	A06				D04197J	9			ALL
2503ZI			AC	0-0	23-22-11	D04285P	B13				D04197J	11			ALL
2503ZO			AC	0-0	23-22-11	D04285P	PERG	1F			D04197J	S/R			ALL
2505B	24	M5	AE	20-2	34-31-21	D04285P	B07				D04273J	2			ALL
2505R	24	M5	AE	0-0	34-31-21	D04285P	A07				D04273J	1			ALL
2505ZI			AE	0-0	34-31-21	D04285P	B08				D04273J	3			ALL
2505ZO			AE	0-0	34-31-21	D04285P	PERG	1F			D04273J	S/R			ALL
2506B	24	M5	AF	20-2	34-51-21	D04285P	B09				D04273J	5			ALL
2506R	24	M5	AF	0-0	34-51-21	D04285P	A09				D04273J	4			ALL
2506ZI			AF	0-0	34-51-21	D04285P	A08				D04273J	6			ALL
2506ZO			AF	0-0	34-51-21	D04285P	PERG	1F			D04273J	S/R			ALL
2507B	24	M5	AG	29-1	23-12-21	D04285P	B10				D04197J	2			YC051-YC055
2507R	24	M5	AG	29-2	23-12-21	D04285P	B10				D04197J	2			YC056-YR328
2507ZI			AG	0-0	23-12-21	D04285P	A10				D04197J	1			ALL
2507ZO			AG	0-0	23-12-21	D04285P	B11				D04197J	3			ALL
2508B	24	M5	AH	29-1	23-12-21	D04285P	PERG	1F			D04197J	S/R			ALL
2508R	24	M5	AH	29-2	23-12-21	D04285P	B12				D04197J	5			YC051-YC055
2508ZI			AH	0-0	23-12-21	D04285P	B12				D04197J	5			YC056-YR328
2508ZO			AH	0-0	23-12-21	D04285P	A12				D04197J	4			ALL
2518B	24	M5	AJ	28-0	23-11-21	D04285P	A11				D04197J	6			ALL
2518R	24	M5	AV	105-2	23-11-21	D04285P	PERG	1F			D04197J	S/R			ALL
2518B	24	M5	AV	105-2	23-11-21	D04285P	B18				D08002P	B01			YD158-YD170
2518B	24	M5	AV	105-2	23-11-21	D04285P	B18				D40119P	B01			YL951-YL999, YR301-YR328
2518B	24	M5	AV	86-0	23-11-21	D04285P	B18				D40119P	B01			YN231-YN501
2518R	24	M5	AJ	0-0	23-11-21	D04285P	A18				D08002P	A01			YD158-YD170
2518R	24	M5	AV	0-0	23-11-21	D04285P	A18				D40119P	A01			YL951-YR328
2518ZI			AJ	0-0	23-11-21	D04285P	B16				D08002P	A02			YD158-YD170
2518ZI			AV	0-0	23-11-21	D04285P	B16				D40119P	A02			YL951-YR328
2518ZO			AJ	0-0	23-11-21	D04285P	PERG	1F			D08002P	PERG	1F		YD158-YD170
2518ZO			AV	0-0	23-11-21	D04285P	PERG	1F			D40119P	PERG	1F		YL951-YR328
2519B	24	M5	AK	28-0	23-11-21	D04285P	B19				D08002P	B03			YD158-YD170
2519B	24	M5	AW	105-2	23-11-21	D04285P	B19				D40119P	B03			YL951-YL999, YR301-YR328
2519B	24	M5	AW	86-0	23-11-21	D04285P	B19				D40119P	B03			YN231-YN501
2519R	24	M5	AK	0-0	23-11-21	D04285P	A19				D08002P	A03			YD158-YD170
2519R	24	M5	AW	0-0	23-11-21	D04285P	A19				D40119P	A03			YL951-YR328
2519ZI			AK	0-0	23-11-21	D04285P	A20				D08002P	A04			YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W5190

Page 2

Nov 12/2012



WIRE LIST
D280A108

91-21-11
Section W5190
Page 3
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5191	286A5191			E4-1 AUDIO NO. 2 (continued)											
2549B	24	M5	AJ		86-0	SPARE	D04285P	B14			D40119P	B07			YN231-YN501
2549R	24	M5	AJ		0-0	SPARE	D04285P	A14			D40119P	A07			YL951-YR328
2549ZI			AJ		0-0	SPARE	D04285P	A16			D40119P	A08			YL951-YR328
2549ZO			AJ		0-0	SPARE	D04285P	PERG	1F		D40119P	PERG	1F		YL951-YR328
2550B	24	M5	AI		6-2	SPARE	D04277P	B03			D04285P	B14			YD158-YD170
2550R	24	M5	AI		0-0	SPARE	D04277P	A03			D04285P	A14			YD158-YD170
2550ZI			AI		0-0	SPARE	D04277P	B04			D04285P	B15			YD158-YD170
2550ZO			AI		0-0	SPARE	D04277P	PERG	1F		D04285P	PERG	1F		YD158-YD170
2551B	24	M5	AN		7-3	SPARE	D43331P	B10			D04289P	B10			YD158-YD170
2551R	24	M5	AN		0-0	SPARE	D43331P	A10			D04289P	A10			YD158-YD170
2551ZI			AN		0-0	SPARE	D43331P	B11			D04289P	B11			YD158-YD170
2551ZO			AN		0-0	SPARE	D43331P	PERG	1F		D04289P	PERG	1F		YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W5190

Page 4 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To					
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W5202	286A5202	AP0900A BRKT TO GLARESHIELD DIMMER CONTROL UNITS (P9) RN2														
5501	20	PA			6-3	33-14-11	D11932		11		D40944P	3			ALL	
5502	20	PA			2-6	33-14-11	D11932		12		GD0911C	AC..	1A		ALL	
5503	20	PA			6-3	33-14-11	D11932		5		D40944P	4			ALL	
5504	20	PA			6-3	33-14-11	D11932		6		D40944P	5			ALL	
5505	20	PA			6-3	33-14-11	D11932		1		D40944P	6			ALL	
5506	20	PA			2-6	33-14-11	D11932		10		GD0911C	DC..	1A		ALL	
5507	20	PA			2-6	33-14-11	D11932		7		GD0911C	ST..	1A		ALL	
5508	20	PA			6-3	33-14-11	D11932		24		D40944P	12			ALL	
5509	20	PA			6-3	33-14-11	D11932		2		D40944P	11			ALL	
5510	20	PA			2-0	33-14-11	D11930		11		SM00001		S		ALL	
5511	20	PA			2-4	33-14-11	D11930		12		GD0901C	AC..	1A		ALL	
5512	20	PA			2-0	33-14-11	D11930		5		SM00004		S		ALL	
5513	20	PA			2-0	33-14-11	D11930		6		SM00003		S		ALL	
5514	20	PA			2-0	33-14-11	D11930		1		SM00002		S		ALL	
5515	20	PA			2-4	33-14-11	D11930		10		GD0901C	DC..	1A		ALL	
5516	20	PA			2-4	33-14-11	D11930		7		GD0901C	ST..	1A		ALL	
5517	20	PA			3-0	33-14-11	D11930		8		D40944P	18			ALL	
5518	20	PA			3-0	33-14-11	D11930		2		D40944P	16			ALL	
5519	20	PA			3-0	33-14-11	D12592		9		D40944P	20			ALL	
5520	20	PA			3-0	33-14-11	D11930		24		D40944P	17			ALL	
5521	20	PA			3-0	33-14-11	D12592		18		D40944P	21			ALL	
5522	20	PA			3-0	33-14-11	D11930		23		D40944P	19			ALL	
5523	20	PA			2-6	33-14-11	D11932		20		GD0911C	DC..	1A		ALL	
5524	20	PA			2-4	33-14-11	D11930		20		GD0901C	DC..	1A		ALL	
5525	20	PA			1-7	33-14-11	D40944P		7		SM00001		S		ALL	
5526	20	PA			1-7	33-14-11	D40944P		10		SM00002		S		ALL	
5527	20	PA			1-7	33-14-11	D40944P		9		SM00003		S		ALL	
5528	20	PA			1-7	33-14-11	D40944P		8		SM00004		S		ALL	
5529	20	PA			2-0	33-14-11	D12592		11		SM00001		S		ALL	
5530	20	PA			2-0	33-14-11	D12592		1		SM00002		S		ALL	
5531	20	PA			2-0	33-14-11	D12592		6		SM00003		S		ALL	
5532	20	PA			2-0	33-14-11	D12592		5		SM00004		S		ALL	
5533	20	PA			2-4	33-14-11	D12592		12		GD0901C	AC..	1A		ALL	
5534	20	PA			2-4	33-14-11	D12592		20		GD0901C	DC..	1A		ALL	
5535	20	PA			2-4	33-14-11	D12592		10		GD0901C	DC..	1A		ALL	
5536	20	PA			2-4	33-14-11	D12592		7		GD0901C	ST..	1A		ALL	

WIRE LIST

D280A108

91-21-11
Section W5200
Page 1
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To															
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity						
W5204	286A5204	NITROGEN GEN SYSTEM E1-4 TO AC0538																	
0001	20	CQ		55-2 47-30-11	D40332J				D13928	16			YD160-YL999, YR301-YR328						
0001	20	CQ		44-9 47-30-11	D40332J				D13928	16			YN231-YN501						
0002	20	PA		55-2 SPARE	D40332J				D13928	17			YD160-YL999, YR301-YR328						
0002	20	PA		44-9 SPARE	D40332J				D13928	17			YN231-YN501						
0003	20	PA		55-2 47-30-11	D40332J				D13928	13			YD160-YL999, YR301-YR328						
0003	20	PA		44-9 47-30-11	D40332J				D13928	13			YN231-YN501						
0004	20	PA		55-2 47-30-11	D40332J				D13928	24			YD160-YL999, YR301-YR328						
0004	20	PA		44-9 47-30-11	D40332J				D13928	24			YN231-YN501						
0005	20	PA		55-2 47-30-11	D40332J				D13928	22			YD160-YL999, YR301-YR328						
0005	20	PA		44-9 47-30-11	D40332J				D13928	22			YN231-YN501						
0006	20	PA		55-2 47-30-11	D40332J				D13928	9			YD160-YL999, YR301-YR328						
0006	20	PA		44-9 47-30-11	D40332J				D13928	9			YN231-YN501						
0007	20	CQ		55-2 47-30-11	D40332J				D13928	11			YD160-YL999, YR301-YR328						
0007	20	CQ		44-9 47-30-11	D40332J				D13928	11			YN231-YN501						
0008	20	PA		55-2 47-30-11	D40332J				D13928	19			YD160-YL999, YR301-YR328						
0008	20	PA		44-9 47-30-11	D40332J				D13928	19			YN231-YN501						
0009	20	PA		55-2 47-30-11	D40332J				D13928	1			YD160-YL999, YR301-YR328						
0009	20	PA		44-9 47-30-11	D40332J				D13928	1			YN231-YN501						
1001	20	VF	AE	8-3 47-30-11	D13838				TB4601Y	A005	1A		YD160-YR328						
1001Z			AE	0-0 47-30-11	D13838	PERB			GD00662	ST..	1A		YD160-YR328						
1002	20	VF	AF	8-2 47-30-11	D13838				TB4601Y	B001	1A		YD160-YL999, YR301-YR328						
1002	20	VF	AF	8-3 47-30-11	D13838				TB4601Y	B001	1A		YN231-YN501						
1002Z			AF	0-0 47-30-11	D13838	PERB			GD00662	ST..	1A		YD160-YR328						
1003	20	VF	AG	8-2 47-30-11	D13838				TB4601Y	B003	1A		YD160-YL999, YR301-YR328						
1003	20	VF	AG	8-3 47-30-11	D13838				TB4601Y	B003	1A		YN231-YN501						
1003Z			AG	0-0 47-30-11	D13838	PERB			GD00662	ST..	1A		YD160-YR328						
1004	20	VF	AH	8-3 47-30-11	D13838				TB4601Y	B005	1A		YD160-YR328						
1004Z			AH	0-0 47-30-11	D13838	PERB			GD00662	ST..	1A		YD160-YR328						

WIRE LIST

D280A108

91-21-11

Section W5200

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5204	286A5204			NITROGEN GEN SYSTEM E1-4 TO AC0538 (continued)											
1005	20	X1		AK	0-7	47-30-11	TB4601Y	A001	1A		TB4601Y	A003	1A		YD160-YR328
1005Z				AK	0-0	47-30-11	TB4601Y	DED			GD00662	ST..	1A		YD160-YR328
1006	20	X1		AL	1-0	47-30-11	TB4601Y	A003	1A		TB4601Y	A005	1A		YD160-YR328
1006Z				AL	0-0	47-30-11	GD00662	ST..	1A		TB4601Y	DED			YD160-YR328
1007	20	X1		AA	25-8	47-30-11	TB4601Y	A001	1A		D13928	3			YD160-YR328
1007Z				AA	0-0	47-30-11	GD00662	ST..	1A		D13928	PERB			YD160-YR328
1008	20	X1		AB	25-8	47-30-11	TB4601Y	B001	1A		D13928	7			YD160-YR328
1008Z				AB	0-0	47-30-11	GD00662	ST..	1A		D13928	PERB			YD160-YR328
1009	20	X1		AC	25-8	47-30-11	TB4601Y	B003	1A		D13928	2			YD160-YR328
1009Z				AC	0-0	47-30-11	GD00662	ST..	1A		D13928	PERB			YD160-YR328
1010	20	X1		AD	25-9	47-30-11	TB4601Y	B005	1A		D13928	5			YD160-YL999, YR301-YR328
1010	20	X1		AD	25-8	47-30-11	TB4601Y	B005	1A		D13928	5			YN231-YN501
1010Z				AD	0-0	47-30-11	GD00662	ST..	1A		D13928	PERB			YD160-YR328
W5205	286A5205			EE INTER-RACK-LEFT (E1-1,E1-2,E3-1,E3-2,E5-2)											
0001	22	PA			12-3	34-51-41	D45203P	A01			D45201J	1			YC051-YD158, YL951-YR328
0002	22	PA			12-3	34-51-41	D45203P	A02			D45201J	2			YC051-YD158, YL951-YR328
0003	22	PA			10-7	34-51-41	D45203P	A03			D02119	E			YC051-YD158, YL951-YR328
0004	22	PA			10-7	34-51-41	D45203P	A04			D02119	D			YC051-YD158, YL951-YR328
0005	22	PA			12-3	34-51-41	D45203P	A05			D45201J	5			YC051-YD158, YL951-YR328
0006	22	PA			12-3	SPARE	D45203P	A06			D45201J	6			YC051-YD158, YL951-YR328
0007	22	PA			12-3	34-51-41	D45203P	A07			D45201J	7			YC051-YD158, YL951-YR328
0008	22	PA			10-7	34-51-41	D45203P	A08			D02119	A			YC051-YD158, YL951-YR328
0009	20	PA			1-6	34-51-41	GD00315	DC..	E		D02119	C			YC051-YD158, YL951-YR328
0010	22	PA			12-3	SPARE	D45203P	A10			D45201J	10			YC051-YD158, YL951-YR328
0011	22	PA			29-1	34-51-41	D45205P	A01			D45201J	11			YC051-YC055
0011	22	PA			28-11	34-51-41	D45205P	A01			D45201J	11			YC056-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5200

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5205	286A5205			EE INTER-RACK-LEFT (E1-1,E1-2,E3-1,E3-2,E5-2) (continued)											
0012	22		PA		12-3	34-51-41	D45203P	B04			D45201J	17			YL951-YR328
0013	22		PA		13-5	23-32-21	D45203P	A09			D45209J	A10			YL951-YL967, YN231-YN235
0013	22		PA		13-5	SPARE	D45203P	A09			D45209J	A10			YL968-YL999, YN236-YN260
0014	22		PA		13-5	23-32-21	D45203P	B09			D45209J	B10			YL951-YL967, YN231-YN235
0014	22		PA		13-5	SPARE	D45203P	B09			D45209J	B10			YL968-YL999, YN236-YN260
0021	16		PA		13-10	34-21-11	D45203P	F			D45209J	F			YC051-YC055
0021	16		PA		13-5	34-21-11	D45203P	F			D45209J	F			YC056-YD158, YL951-YR328
0022	20		PA		30-8	34-21-11	D45205P	A02			D45209J	A02			YC051-YC055
0022	20		PA		30-1	34-21-11	D45205P	A02			D45209J	A02			YC056-YD158, YL951-YR328
0024	20		PA		30-8	34-21-11	D45205P	A04			D45209J	A04			YC051-YC055
0024	20		PA		30-1	34-21-11	D45205P	A04			D45209J	A04			YC056-YD158, YL951-YR328
0025	20		PA		30-8	SPARE	D45205P	A05			D45209J	A05			YC051-YC055
0025	20		PA		30-1	SPARE	D45205P	A05			D45209J	A05			YC056-YD158, YL951-YR328
0026	20		PA		30-8	34-61-11	D45205P	A08			D45209J	A08			YC053-YC055
0026	20		PA		30-1	34-61-11	D45205P	A08			D45209J	A08			YC056-YD157
0026	20		CQ		30-1	34-61-11	D45205P	A08			D45209J	A08			YD158, YL951-YR328
0027	20		PA		30-8	34-61-11	D45205P	A09			D45209J	A09			YC053-YC055
0027	20		PA		30-1	34-61-11	D45205P	A09			D45209J	A09			YC056-YD157
0027	20		CQ		30-1	34-61-11	D45205P	A09			D45209J	A09			YD158, YL951-YR328
0041	22		CQ		2-11	49-62-11	D45205P	B01			D45207P	A01			YC051-YD158, YL951-YR328
0053	20		CQ		28-7	SPARE	D45201J	31			D45207P	A03			YC051-YC055
0053	20		CQ		28-5	SPARE	D45201J	31			D45207P	A03			YC056-YD158, YL951-YR328
0063	20		PA		12-3	22-14-11	D45201J	3			D45203P	B01			YC051-YD158, YL951-YR328
2001B	22		X2	AA	30-8	SPARE	D45205P	B03			D45209J	B03			YC051-YC055
2001B	22		X2	AA	30-1	SPARE	D45205P	B03			D45209J	B03			YC056-YD158, YL951-YR328
2001R	22		X2	AA	0-0	SPARE	D45205P	B02			D45209J	B02			YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5200

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Description Fam FT-IN Diagram		From Equip Term Type Splice				To Equip Term Type Splice Effectivity				
W5205	286A5205			EE INTER-RACK-LEFT (E1-1,E1-2,E3-1,E3-2,E5-2) (continued)										
2001Z			AA	0-0	SPARE	D45205P	PERG	1F	D45209J	PERG	1F	YC051-YD158, YL951-YR328		
2002B	24	Y2	BB	13-5	34-21-14	D45203P	B08		D45209J	B08		YD158, YL951-YR328		
2002R	24	Y2	BB	0-0	34-21-14	D45203P	B07		D45209J	B07		YD158, YL951-YR328		
2002Z			BB	0-0	34-21-14	D45203P	PERG	1F	D45209J	PERG	1F	YD158, YL951-YR328		
2005B	24	Y2	AB	12-3	31-62-11	D45203P	B09		D45201J	30		YC051-YD157		
2005R	24	Y2	AB	0-0	31-62-11	D45203P	A09		D45201J	29		YC051-YD157		
2005Z			AB	0-0	31-62-11	D45203P	PERG	1F	D45201J	S/R		YC051-YD157		
2006B	22	X2	AF	12-3	SPARE	D45203P	B06		D45201J	16		YC051-YD158, YL951-YR328		
2006R	22	X2	AF	0-0	SPARE	D45203P	B05		D45201J	15		YC051-YD158, YL951-YR328		
2006Z			AF	0-0	SPARE	D45203P	PERG	1F	D45201J	S/R		YC051-YD158, YL951-YR328		
2007B	20	X2	AG	21-7	27-25-11	D45207P	B10		D45203P	B02		YD154-YD158, YL951-YR328		
2007R	20	X2	AG	0-0	27-25-11	D45207P	A10		D45203P	B03		YD154-YD158, YL951-YR328		
2007Z			AG	0-0	27-25-11	D45207P	PERG	1F	D45203P	PERG	1F	YD154-YD158, YL951-YR328		
2021B	22	X2	AU	2-11	49-62-11	D45205P	A06		D45207P	B06		YC051-YD158, YL951-YR328		
2021R	22	X2	AU	0-0	49-62-11	D45205P	B05		D45207P	A05		YC051-YD158, YL951-YR328		
2021Z			AU	0-0	49-62-11	D45205P	PERG	1F	D45207P	PERG	1F	YC051-YD158, YL951-YR328		
2022B	22	X2	AV	2-11	49-62-11	D45205P	B08		D45207P	A08		YC051-YD158, YL951-YR328		
2022R	22	X2	AV	0-0	49-62-11	D45205P	B07		D45207P	A07		YC051-YD158, YL951-YR328		
2022Z			AV	0-0	49-62-11	D45205P	PERG	1F	D45207P	PERG	1F	YC051-YD158, YL951-YR328		
2031B	24	Y2	BA	5-2	SPARE	D45209J	A07		D45201J	13		YC051-YC055		
2031B	24	Y2	BA	4-5	SPARE	D45209J	A07		D45201J	13		YC056-YD158, YL951-YR328		
2031R	24	Y2	BA	0-0	SPARE	D45209J	A06		D45201J	12		YC051-YD158, YL951-YR328		
2031Z			BA	0-0	SPARE	D45209J	PERG	1F	D45201J	S/R		YC051-YD158, YL951-YR328		

WIRE LIST
D280A108

91-21-11
Section W5200
Page 5
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5208	286A5208			NGS CONTROLLER TO PRESS SEALS AND AC0538											
0001	20		PA		1-4	47-30-11	D13804	47			SM00001		W		YD160-YL955, YN232-YN235
0001	20		PA		1-5	47-30-11	D13804	47			SM00001		W		YL956-YL999, YN236-YR328
0002	20		PA		1-4	47-30-11	D13804	30			SM00001		W		YD160-YL955, YN232-YN235
0002	20		PA		1-5	47-30-11	D13804	30			SM00001		W		YL956-YL999, YN236-YR328
0003	20		PA		1-4	47-30-11	D13804	29			SM00001		W		YD160-YL955, YN232-YN235
0003	20		PA		1-5	47-30-11	D13804	29			SM00001		W		YL956-YL999, YN236-YR328
0004	20		PA		1-4	47-30-11	D13804	46			SM00001		W		YD160-YL955, YN232-YN235
0004	20		PA		1-5	47-30-11	D13804	46			SM00001		W		YL956-YL999, YN236-YR328
0005	20		PA		11-2	47-30-11	D13934	18			GD00121	DC..	E		YD160-YL999, YN232-YR328
0006	20		PA		2-6	47-30-11	D13806	45			GD00091	ST..	E		YD160-YL999, YN232-YR328
0021	20		PA		2-0	47-30-11	D13806	29			GD00121	DC..	E	*	YD160-YL999, YN232-YR328
0022	20		PA		2-0	47-30-11	D13806	47			GD00121	DC..	E	*	YD160-YL999, YN232-YR328
0023	20		PA		2-0	47-30-11	D13806	48			GD00121	DC..	E	*1	YD160-YL999, YN232-YR328
0024	20		PA		2-0	47-30-11	D13806	49			GD00121	DC..	E	*1	YD160-YL999, YN232-YR328
1501	20	X1		CD	16-3	47-30-11	D13970	4			D13804		52		YD160-YL999, YN232-YR328
1501Z				CD	0-0	47-30-11	D13970	PERB			D13804		PERB		YD160-YL999, YN232-YR328
1502	20	X1		CN	7-6	47-30-11	D13832	24			D13806		9		YD160-YL999, YN232-YR328
1502Z				CN	0-0	47-30-11	D13832	PERB			D13806		PERB		YD160-YL999, YN232-YR328
1503	20	X1		CP	7-6	47-30-11	D13832	19			D13806		52		YD160-YL999, YN232-YR328

WIRE LIST

D280A108

91-21-11

Section W5200

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5208	286A5208				NGS CONTROLLER TO PRESS SEALS AND AC0538 (continued)										
1503Z				CP	0-0	47-30-11	D13832	PERB			D13806	PERB			YD160-YL999, YN232-YR328
1504	20	X1		CR	7-6	47-30-11	D13832	13			D13806	16			YD160-YL999, YN232-YR328
1504Z				CR	0-0	47-30-11	D13832	PERB			D13806	PERB			YD160-YL999, YN232-YR328
1505	20	X1		CS	7-6	47-30-11	D13832	11			D13806	23			YD160-YL999, YN232-YR328
1505Z				CS	0-0	47-30-11	D13832	PERB			D13806	PERB			YD160-YL999, YN232-YR328
1506	20	X1		CT	7-6	47-30-11	D13832	17			D13806	41			YD160-YL999, YN232-YR328
1506Z				CT	0-0	47-30-11	D13832	PERB			D13806	PERB			YD160-YL999, YN232-YR328
1507	20	X1		CU	7-6	47-30-11	D13832	9			D13806	33			YD160-YL999, YN232-YR328
1507Z				CU	0-0	47-30-11	D13832	PERB			D13806	PERB			YD160-YL999, YN232-YR328
1508	20	X1		CV	7-6	47-30-11	D13832	6			D13806	40			YD160-YL999, YN232-YR328
1508Z				CV	0-0	47-30-11	D13832	PERB			D13806	PERB			YD160-YL999, YN232-YR328
1509	20	X1		CW	7-6	47-30-11	D13832	1			D13806	12			YD160-YL999, YN232-YR328
1509Z				CW	0-0	47-30-11	D13832	PERB			D13806	PERB			YD160-YL999, YN232-YR328
1510	20	X1		FA	1-7	47-30-11	D13832	22			SM00003	9			YD160-YL955, YN232-YN235
1510	20	X1		FA	2-0	47-30-11	D13832	22			SM00003	9			YL956-YL999, YN236-YR328
1510Z				FA	0-0	47-30-11	D13832	PERB			SM00013	S			YD160-YL999, YN232-YR328
1511	20	X1		FB	6-6	47-30-11	D13806	3			SM00003	9			YD160-YL955, YN232-YN235
1511	20	X1		FB	6-1	47-30-11	D13806	3			SM00003	9			YL956-YL999, YN236-YR328
1511Z				FB	0-0	47-30-11	D13806	PERB			SM00013	S			YD160-YL999, YN232-YR328

WIRE LIST
D280A108

91-21-11
Section W5200
Page 7
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5208	286A5208			NGS CONTROLLER TO PRESS SEALS AND AC0538 (continued)											
1512	20	X1	FC		6-6	47-30-11	D13806	27			SM00003		9		YD160-YL955, YN232-YN235
1512	20	X1	FC		6-1	47-30-11	D13806	27			SM00003		9		YL956-YL999, YN236-YR328
1512Z			FC		0-0	47-30-11	D13806	PERB			SM00013		S		YD160-YL999, YN232-YR328
1513	20	X1	FD		6-6	47-30-11	D13806	8			SM00003		9		YD160-YL955, YN232-YN235
1513	20	X1	FD		6-1	47-30-11	D13806	8			SM00003		9		YL956-YL999, YN236-YR328
1513Z			FD		0-0	47-30-11	D13806	PERB			SM00013		S		YD160-YL999, YN232-YR328
1514	20	X1	FE		1-7	47-30-11	D13832	16			SM00002		9		YD160-YL955, YN232-YN235
1514	20	X1	FE		2-0	47-30-11	D13832	16			SM00002		9		YL956-YL999, YN236-YR328
1514Z			FE		0-0	47-30-11	D13832	PERB			SM00012		S		YD160-YL999, YN232-YR328
1515	20	X1	FF		6-6	47-30-11	D13806	46			SM00002		9		YD160-YL955, YN232-YN235
1515	20	X1	FF		6-1	47-30-11	D13806	46			SM00002		9		YL956-YL999, YN236-YR328
1515Z			FF		0-0	47-30-11	D13806	PERB			SM00012		S		YD160-YL999, YN232-YR328
1516	20	X1	FG		6-6	47-30-11	D13806	28			SM00002		9		YD160-YL955, YN232-YN235
1516	20	X1	FG		6-1	47-30-11	D13806	28			SM00002		9		YL956-YL999, YN236-YR328
1516Z			FG		0-0	47-30-11	D13806	PERB			SM00012		S		YD160-YL999, YN232-YR328
1517	20	X1	FJ		5-5	47-30-11	D13934	6			SM00002		9		YD160-YL955, YN232-YN235
1517	20	X1	FJ		6-4	47-30-11	D13934	6			SM00002		9		YL956-YL999, YN236-YR328
1517Z			FJ		0-0	47-30-11	D13934	PERB			SM00012		S		YD160-YL999, YN232-YR328
1518	20	X1	FK		11-4	47-30-11	D13934	39			D13806		31		YD160-YL999, YN232-YR328

WIRE LIST

D280A108

91-21-11

Section W5200

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5208	286A5208				NGS CONTROLLER TO PRESS SEALS AND AC0538 (continued)										
1518Z				FK	0-0	47-30-11	D13934	PERB			D13806	PERB			YD160-YL999, YN232-YR328
1519	20	X1	FL		11-4	47-30-11	D13934	38			D13806	30			YD160-YL999, YN232-YR328
1519Z			FL		0-0	47-30-11	D13934	PERB			D13806	PERB			YD160-YL999, YN232-YR328
1520	20	X1	FM		11-4	47-30-11	D13934	24			D13806	15			YD160-YL999, YN232-YR328
1520Z			FM		0-0	47-30-11	D13934	PERB			D13806	PERB			YD160-YL999, YN232-YR328
1521	20	X1	FN		11-0	47-30-11	D13934	36			D13804	44			YD160-YL999, YN232-YR328
1521Z			FN		0-0	47-30-11	D13934	PERB			D13804	PERB			YD160-YL999, YN232-YR328
1522	20	X1	FP		11-0	47-30-11	D13934	15			D13804	42			YD160-YL999, YN232-YR328
1522Z			FP		0-0	47-30-11	D13934	PERB			D13804	PERB			YD160-YL999, YN232-YR328
1523	20	X1	CL		11-4	47-30-11	D13934	8			D13806	6			YD160-YL999, YN232-YR328
1523Z			CL		0-0	47-30-11	D13934	PERB			D13806	PERB			YD160-YL999, YN232-YR328
1524	20	X1	FH		11-4	47-30-11	D13934	19			D13806	14			YD160-YL999, YN232-YR328
1524Z			FH		0-0	47-30-11	D13934	PERB			D13806	PERB			YD160-YL999, YN232-YR328
2001B	20	X2	CC		16-3	47-30-11	D13970	39			D13804	31			YD160-YL999, YN232-YR328
2001R	20	X2	CC		0-0	47-30-11	D13970	20			D13804	49			YD160-YL999, YN232-YR328
2001Z			CC		0-0	47-30-11	D13970	PERB			D13804	PERB			YD160-YL999, YN232-YR328
2002B	20	X2	CE		11-0	47-30-11	D13934	4			D13804	26			YD160-YL999, YN232-YR328
2002R	20	X2	CE		0-0	47-30-11	D13934	13			D13804	25			YD160-YL999, YN232-YR328
2002Z			CE		0-0	47-30-11	D13934	PERB			D13804	PERB			YD160-YL999, YN232-YR328

WIRE LIST
D280A108

91-21-11
Section W5200
Page 9
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram		From				To				Effectivity
	GA	CO	TY		Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W5208	286A5208			NGS CONTROLLER TO PRESS SEALS AND AC0538 (continued)											
2003B	20	X2	CF	11-0	47-30-11	D13934	30			D13804	10			YD160-YL999, YN232-YR328	
2003R	20	X2	CF	0-0	47-30-11	D13934	31			D13804	23			YD160-YL999, YN232-YR328	
2003Z			CF	0-0	47-30-11	D13934	PERB			D13804	PERB			YD160-YL999, YN232-YR328	
2004B	20	X2	CG	11-0	47-30-11	D13934	32			D13804	11			YD160-YL999, YN232-YR328	
2004R	20	X2	CG	0-0	47-30-11	D13934	33			D13804	24			YD160-YL999, YN232-YR328	
2004Z			CG	0-0	47-30-11	D13934	PERB			D13804	PERB			YD160-YL999, YN232-YR328	
2005B	20	X2	CH	11-0	47-30-11	D13934	26			D13804	8			YD160-YL999, YN232-YR328	
2005R	20	X2	CH	0-0	47-30-11	D13934	27			D13804	7			YD160-YL999, YN232-YR328	
2005Z			CH	0-0	47-30-11	D13934	PERB			D13804	PERB			YD160-YL999, YN232-YR328	
2006B	20	X2	CJ	11-0	47-30-11	D13934	28			D13804	3			YD160-YL999, YN232-YR328	
2006R	20	X2	CJ	0-0	47-30-11	D13934	29			D13804	2			YD160-YL999, YN232-YR328	
2006Z			CJ	0-0	47-30-11	D13934	PERB			D13804	PERB			YD160-YL999, YN232-YR328	
2007B	20	X2	CK	11-4	47-30-11	D13934	21			D13806	34			YD160-YL999, YN232-YR328	
2007R	20	X2	CK	0-0	47-30-11	D13934	20			D13806	35			YD160-YL999, YN232-YR328	
2007Z			CK	0-0	47-30-11	D13934	PERB			D13806	PERB			YD160-YL999, YN232-YR328	
3001B	20	X3	CB	16-3	47-30-11	D13970	36			D13804	51			YD160-YL999, YN232-YR328	
3001R	20	X3	CB	0-0	47-30-11	D13970	34			D13804	32			YD160-YL999, YN232-YR328	
3001Y	20	X3	CB	0-0	47-30-11	D13970	32			D13804	48			YD160-YL999, YN232-YR328	
3001Z			CB	0-0	47-30-11	D13970	PERB			D13804	PERB			YD160-YL999, YN232-YR328	

WIRE LIST

D280A108

91-21-11

Section W5200

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5208	286A5208			NGS CONTROLLER TO PRESS SEALS AND AC0538 (continued)											
4001B	20	X4	CA		16-3	47-30-11	D13970		22		D13804		16		YD160-YL999, YN232-YR328
4001G	20	X4	CA		0-0	47-30-11	D13970		24		D13804		17		YD160-YL999, YN232-YR328
4001R	20	X4	CA		0-0	47-30-11	D13970		26		D13804		50		YD160-YL999, YN232-YR328
4001Y	20	X4	CA		0-0	47-30-11	D13970		28		D13804		15		YD160-YL999, YN232-YR328
4001Z			CA		0-0	47-30-11	D13970		PERB		D13804		PERB		YD160-YL999, YN232-YR328
4002B	20	X4	CM		7-6	47-30-11	D13832		7		D13806		11		YD160-YL999, YN232-YR328
4002G	20	X4	CM		0-0	47-30-11	D13832		3		D13806		44		YD160-YL999, YN232-YR328
4002R	20	X4	CM		0-0	47-30-11	D13832		2		D13806		24		YD160-YL999, YN232-YR328
4002Y	20	X4	CM		0-0	47-30-11	D13832		5		D13806		25		YD160-YL999, YN232-YR328
4002Z			CM		0-0	47-30-11	D13832		PERB		D13806		PERB		YD160-YL999, YN232-YR328

WIRE LIST
D280A108

91-21-11
Section W5200
Page 11 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5222		286A5222			DISC AB0500DL TO MAIN WHEEL WELL											
0504		20		PA		21-1	29-11-11	D40302P	13			D46030J	10			ALL
0505		20		PA		21-1	29-11-11	D40302P	14			D46030J	2			ALL
0506		22		PA		21-1	29-33-11	D40318P	15			D46030J	11			ALL
0507		22		PA		21-1	29-33-11	D40318P	16			D46030J	9			ALL
0508		22		PA		21-1	31-62-14	D46030J	1			D40318P	23			ALL
0511		20		PA		25-8	32-44-11	D46032J	8			D40302P	1			YC051-YL999, YR301-YR328
0511		20		PA		25-7	32-44-11	D46032J	8			D40302P	1			YN231-YN501
0513		20		PA		25-8	32-44-11	D46032J	7			D40302P	2			YC051-YL999, YR301-YR328
0513		20		PA		25-7	32-44-11	D46032J	7			D40302P	2			YN231-YN501
0514		20		PA		25-8	32-44-11	D46032J	10			D40302P	3			YC051-YL999, YR301-YR328
0514		20		PA		25-7	32-44-11	D46032J	10			D40302P	3			YN231-YN501
0516		20		PA		25-8	32-44-11	D46032J	11			D40302P	4			YC051-YL999, YR301-YR328
0516		20		PA		25-7	32-44-11	D46032J	11			D40302P	4			YN231-YN501
0517		20		PA		25-8	32-44-11	D46032J	9			D40302P	5			YC051-YL999, YR301-YR328
0517		20		PA		25-7	32-44-11	D46032J	9			D40302P	5			YN231-YN501
0518		20		CQ		36-0	27-23-11	D46032J	12			D40266J	1			YC051-YL999, YR301-YR328
0518		20		CQ		36-1	27-23-11	D46032J	12			D40266J	1			YN231-YN501
0519		20		CQ		36-0	27-23-11	D46032J	13			D40266J	2			YC051-YL999, YR301-YR328
0519		20		CQ		36-1	27-23-11	D46032J	13			D40266J	2			YN231-YN501
0520		20		CQ		36-0	27-23-14	D46032J	14			D40266J	3			YC051-YC064
0520		20		CQ		35-1	27-23-14	SM00001		S		D40266J	3			YC065-YL999, YR301-YR328
0520		20		CQ		35-2	27-23-14	SM00001		S		D40266J	3			YN231-YN501
0521		20		PA		36-0	29-31-11	D46032J	2			D40266J	5			YC051-YL999, YR301-YR328
0521		20		PA		36-1	29-31-11	D46032J	2			D40266J	5			YN231-YN501
0522		20		PA		36-0	29-31-11	D46032J	3			D40266J	6			YC051-YL999, YR301-YR328
0522		20		PA		36-1	29-31-11	D46032J	3			D40266J	6			YN231-YN501
0523		20		PA		36-0	29-31-11	D46032J	1			D40266J	4			YC051-YL999, YR301-YR328
0523		20		PA		36-1	29-31-11	D46032J	1			D40266J	4			YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W5220

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W5222	286A5222				DISC AB0500DL TO MAIN WHEEL WELL (continued)											
0524	20		CQ		24-6	31-31-15		SM00001		S		D40318P	24			YC065-YR328
0525	20		CQ		1-9	27-23-14		D46032J	14			SM00001		S		YC065-YR328
0591	20		PA		25-8	32-41-11		D46032J	4			D40302P	6			YC051-YL999, YR301-YR328
0591	20		PA		25-7	32-41-11		D46032J	4			D40302P	6			YN231-YN501
0592	20		PA		20-10	32-41-11		D46032J	5			GD05108	DC..	1		YC051-YL999, YR301-YR328
0592	20		PA		21-1	32-41-11		D46032J	5			GD05108	DC..	1		YN231-YN501
1101R	20		X5	BN	25-8	26-12-11		D46032J	6			D40302P	15			YC051-YL999, YR301-YR328
1101R	20		X5	BN	25-7	26-12-11		D46032J	6			D40302P	15			YN231-YN501
1101Z				BN	0-0	26-12-11		D46032J		DED		D40302P	DED			ALL
2601B	20		PB	SA	21-1	78-34-11		D40318P	8			D46030J	17			ALL
2601R	20		PB	SA	0-0	78-34-11		D40318P	7			D46030J	18			ALL
2602B	20		PB	SB	21-1	78-34-11		D40318P	9			D46030J	19			ALL
2602R	20		PB	SB	0-0	78-34-11		D40318P	10			D46030J	7			ALL
2603B	20		PB	SC	21-1	78-36-11		D40318P	20			D46030J	12			ALL
2603R	20		PB	SC	0-0	78-36-11		D40318P	19			D46030J	14			ALL
2604B	20		PB	SD	21-1	78-36-11		D40318P	22			D46030J	6			ALL
2604R	20		PB	SD	0-0	78-36-11		D40318P	21			D46030J	15			ALL
6001	20		PA		21-1	78-34-11		D40318P	17			D46030J	4			ALL
6002	20		PA		16-1	78-34-11		D46030J	3			GD05108	DC..	1		YC051-YL999, YR301-YR328
6002	20		PA		16-5	78-34-11		D46030J	3			GD05108	DC..	1		YN231-YN501
6003R	20		PH		21-1	26-12-11		D46030J	8			D40318P	18			ALL
6004	20		PA		16-1	78-36-11		D46030J	13			GD05108	DC..	1		YC051-YL999, YR301-YR328
6004	20		PA		16-5	78-36-11		D46030J	13			GD05108	DC..	1		YN231-YN501
6005	20		PA		16-1	78-36-11		D46030J	16			GD05108	DC..	1		YC051-YL999, YR301-YR328
6005	20		PA		16-5	78-36-11		D46030J	16			GD05108	DC..	1		YN231-YN501
W5224	286A5224				MAIN WHEEL WELL TO AB0500DL AND CROWN											
0030	20		PA		25-6	31-31-15		D46010J	8			D40416P	8			YC065-YL999, YR301-YR328
0030	20		PA		25-4	31-31-15		D46010J	8			D40416P	8			YN231-YN501
0500	20		PA		15-9	27-41-12		D40250P	6			SP00124		S		YC059-YC064
0500	20		PA		15-7	27-41-12		D40250P	6			SP00124		S		YC065-YN260
0500	20		PA		14-4	27-41-12		D43404P	6			SP00124		S		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W5220

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5224	286A5224			MAIN WHEEL WELL TO AB0500DL AND CROWN (continued)											
0501	20		PA		25-6	27-23-11	D40416P		1		D46010J		4		YC051-YL999, YR301-YR328
0501	20		PA		25-4	27-23-11	D40416P		1		D46010J		4		YN231-YN501
0502	20		PA		25-6	27-23-11	D40416P		2		D46010J		5		YC051-YL999, YR301-YR328
0502	20		PA		25-4	27-23-11	D40416P		2		D46010J		5		YN231-YN501
0503	22		PA		21-0	27-23-14	D40312P		1		D46010J		9		YC051-YC058, YC065-YL999, YR301-YR328
0503	22		PA		20-11	27-23-14	D40312P		1		D46010J		9		YC059-YC064
0503	22		PA		20-10	27-23-14	D40312P		1		D46010J		9		YN231-YN501
0506	20		PA		25-6	27-61-11	D40416P		6		D46010J		6		YC051-YL999, YR301-YR328
0506	20		PA		25-4	27-61-11	D40416P		6		D46010J		6		YN231-YN501
0507	20		PA		25-6	27-61-11	D40416P		3		D46010J		7		YC051-YL999, YR301-YR328
0507	20		PA		25-4	27-61-11	D40416P		3		D46010J		7		YN231-YN501
0508	20		PA		29-9	27-11-11	D40248P		1		D46010J		2		YC051-YC058, YC065-YL999
0508	20		PA		30-0	27-11-11	D40248P		1		D46010J		2		YC059-YC064
0508	20		PA		32-0	27-11-11	D40248P		1		D46010J		2		YN231-YN501
0508	20		PA		29-10	27-11-11	D40248P		1		D46010J		2		YR301-YR328
0509	20		PA		29-9	27-11-11	D40248P		6		D46010J		3		YC051-YC058, YC065-YL999
0509	20		PA		30-0	27-11-11	D40248P		6		D46010J		3		YC059-YC064
0509	20		PA		32-0	27-11-11	D40248P		6		D46010J		3		YN231-YN501
0509	20		PA		29-10	27-11-11	D40248P		6		D46010J		3		YR301-YR328
0510	20		PA		29-9	27-11-11	D40248P		5		D46010J		1		YC051-YC058, YC065-YL999
0510	20		PA		30-0	27-11-11	D40248P		5		D46010J		1		YC059-YC064
0510	20		PA		32-0	27-11-11	D40248P		5		D46010J		1		YN231-YN501
0510	20		PA		29-10	27-11-11	D40248P		5		D46010J		1		YR301-YR328
0511	16		CQ		24-6	27-53-12	D40248P		2		D46036J		1		YC051-YC058, YC065-YL999
0511	16		CQ		24-9	27-53-12	D40248P		2		D46036J		1		YC059-YC064
0511	16		CQ		24-7	27-53-12	D40248P		2		D46036J		1		YN231-YR328
0512	16		CQ		24-6	27-53-12	D40248P		3		D46036J		2		YC051-YC058, YC065-YL999
0512	16		CQ		24-9	27-53-12	D40248P		3		D46036J		2		YC059-YC064

WIRE LIST

D280A108

91-21-11

Section W5220

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W5224	286A5224	MAIN WHEEL WELL TO AB0500DL AND CROWN (continued)													
0512	16	CQ	24-7	27-53-12	D40248P	3			D46036J	2			YN231-YR328		
0513	16	CQ	24-6	27-53-12	D40248P	4			D46036J	3			YC051-YC058, YC065-YL999		
0513	16	CQ	24-9	27-53-12	D40248P	4			D46036J	3			YC059-YC064		
0513	16	CQ	24-7	27-53-12	D40248P	4			D46036J	3			YN231-YR328		
0514	20	PA	17-3	27-41-12	D40250P	1			D46044J	6			YC051-YC058, YC065-YL999		
0514	20	PA	17-5	27-41-12	D40250P	1			D46044J	6			YC059-YC064		
0514	20	PA	17-9	27-41-12	D40250P	1			D46044J	6			YN231-YN260		
0514	20	PA	16-6	27-41-12	D43404P	1			D46044J	6			YN501		
0514	20	PA	16-1	27-41-12	D43404P	1			D46044J	6			YR301-YR328		
0515	20	PA	17-3	27-41-12	D40250P	2			D46044J	10			YC051-YC058, YC065-YL999		
0515	20	PA	17-5	27-41-12	D40250P	2			D46044J	10			YC059-YC064		
0515	20	PA	17-9	27-41-12	D40250P	2			D46044J	10			YN231-YN260		
0515	20	PA	16-6	27-41-12	D43404P	2			D46044J	10			YN501		
0515	20	PA	16-1	27-41-12	D43404P	2			D46044J	10			YR301-YR328		
0516	20	PA	17-3	27-41-12	D40250P	3			D46044J	9			YC051-YC058		
0516	20	PA	5-3	27-41-12	SP00114		S		D46044J	9			YC059-YC064, YD158-YL999, YR301-YR328		
0516	20	PA	5-2	27-41-12	SP00114		S		D46044J	9			YC065-YD157		
0516	20	PA	6-3	27-41-12	SP00114		S		D46044J	9			YN231-YN501		
0517	20	PA	17-3	27-41-12	D40250P	4			D46044J	8			YC051-YC058		
0517	20	PA	5-3	27-41-12	SP00376		S		D46044J	8			YC059-YC064, YD158-YL999, YR301-YR328		
0517	20	PA	5-2	27-41-12	SP00376		S		D46044J	8			YC065-YD157		
0517	20	PA	6-3	27-41-12	SP00376		S		D46044J	8			YN231-YN501		
0518	20	PA	17-3	27-41-12	D40250P	5			D46044J	7			YC051-YC058		
0518	20	PA	5-3	27-41-12	SP00110		S		D46044J	7			YC059-YC064, YD158-YL999, YR301-YR328		
0518	20	PA	5-2	27-41-12	SP00110		S		D46044J	7			YC065-YD157		
0518	20	PA	6-3	27-41-12	SP00110		S		D46044J	7			YN231-YN501		
0519	20	PA	15-9	27-41-12	D40250P	7			SP00368		S		YC059-YC064		
0519	20	PA	15-7	27-41-12	D40250P	7			SP00368		S		YC065-YN260		
0519	20	PA	14-4	27-41-12	D43404P	7			SP00368		S		YN501-YR328		
0520	20	PA	15-9	27-41-12	D40250P	8			SP00370		S		YC059-YC064		

WIRE LIST

D280A108

91-21-11

Section W5220

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5224		286A5224			MAIN WHEEL WELL TO AB0500DL AND CROWN (continued)											
0520		20		PA		15-7	27-41-12	D40250P	8			SP00370		S		YC065-YN260
0520		20		PA		14-4	27-41-12	D43404P	8			SP00370		S		YN501-YR328
0521		20		PA		34-3	29-23-11	SP00504		S		D46010J	10			YC051-YC058, YC065-YL999, YR301-YR328
0521		20		PA		35-8	29-23-11	SP00504		S		D46010J	10			YC059-YC064
0521		20		PA		35-6	29-23-11	SP00504		S		D46010J	10			YN231-YN501
0523		20		PA		15-9	27-41-12	SP00170		S		D40250P	5			YC059-YC064
0523		20		PA		15-7	27-41-12	SP00170		S		D40250P	5			YC065-YN260
0523		20		PA		14-4	27-41-12	SP00170		S		D43404P	5			YN501-YR328
0524		20		PA		15-9	27-41-12	SP00374		S		D40250P	4			YC059-YC064
0524		20		PA		15-7	27-41-12	SP00374		S		D40250P	4			YC065-YN260
0524		20		PA		14-4	27-41-12	SP00374		S		D43404P	4			YN501-YR328
0525		18		PA		15-9	27-41-12	SP00372		S		D40250P	3			YC059-YC064
0525		18		PA		15-7	27-41-12	SP00372		S		D40250P	3			YC065-YN260
0525		18		PA		14-4	27-41-12	SP00372		S		D43404P	3			YN501-YR328
0535		18		PA		20-4	29-25-11	TB0205W	A009	1		D46010J	11			YC051-YL999, YR301-YR328
0535		18		PA		20-2	29-25-11	TB0205W	A009	1		D46010J	11			YN231-YN501
0536		18		PA		20-5	29-25-11	TB0205V	A013	1		D46010J	12			YC051-YL999, YR301-YR328
0536		18		PA		20-6	29-25-11	TB0205V	A013	1		D46010J	12			YN231-YN501
0568		18		PA		12-3	29-25-11	D40312P	10			TB0205V	A015	1		YC051-YC058, YC065-YL999, YR301-YR328
0568		18		PA		12-2	29-25-11	D40312P	10			TB0205V	A015	1		YC059-YC064
0568		18		PA		12-7	29-25-11	D40312P	10			TB0205V	A015	1		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W5220

Page 5 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W5230	286A5230				E/E BAY TO MWW-SYS B ELEC HYD PUMP											
0001	20		HL		43-1	33-42-11		D01782				D43062P	A01			YC051-YC055
0001	20		HL		43-5	33-42-11		D01782				D43062P	A01			YC056-YD152
0001	20		HL		43-6	33-42-11		D01782				D43062P	A01			YD153-YL968, YR301-YR323, YR325-YR328
0001	20		HL		32-7	33-42-11		D01782				D43062P	A01			YN231-YN236, YN501
0002	20		HL		43-1	33-42-11		D01782				D43062P	A02			YC051-YC055
0002	20		HL		43-5	33-42-11		D01782				D43062P	A02			YC056-YD152
0002	20		HL		43-6	33-42-11		D01782				D43062P	A02			YD153-YL968, YR301-YR323, YR325-YR328
0002	20		HL		32-7	33-42-11		D01782				D43062P	A02			YN231-YN236, YN501
0003	18		HL		43-1	33-42-11		D01782		3	18	D43062P	F			YC051-YC055
0003	18		HL		43-5	33-42-11		D01782		3	18	D43062P	F			YC056-YD152
0003	18		HL		43-6	33-42-11		D01782		3	18	D43062P	F			YD153-YL968, YR301-YR323, YR325-YR328
0003	18		HL		32-7	33-42-11		D01782		3	18	D43062P	F			YN231-YN236, YN501
0004	20		HL		1-11	33-42-11		D01782		4		GD00012	AC..	1		YC051-YL968, YR301-YR323, YR325-YR328
0004	20		HL		2-0	33-42-11		D01782		4		GD00012	AC..	1		YN231-YN236, YN501
0005	20		HL		1-11	33-42-11		D01782		5		GD00012	ST..	1		YC051-YL968, YR301-YR323, YR325-YR328
0005	20		HL		2-0	33-42-11		D01782		5		GD00012	ST..	1		YN231-YN236, YN501
0006	20		HL		0-7	33-42-11		D01782		6		D01782	7			YC051-YL968, YN231-YN236, YN501-YR323, YR325-YR328
0501	18		HA		3-8	29-11-12		D02666		5		GD00322	DC..	E		YC051-YC055
0501	18		HA		3-4	29-11-12		D02666		5		GD00322	DC..	E		YC056-YC058, YD153-YL968, YN231-YN236, YN501-YR323, YR325-YR328
0501	18		HA		3-6	29-11-12		D02666		5		GD00322	DC..	E		YC059-YD152
0502	18		HA		1-7	29-34-11		D02666		7		SM00001		9		YC051-YC055
0502	18		HA		1-11	29-34-11		D02666		7		SM00001		9		YC056-YC058

WIRE LIST

D280A108

91-21-11

Section W5230

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W5230	286A5230				E/E BAY TO MWW-SYS B ELEC HYD PUMP (continued)											
0502	18		HA		2-7	29-34-11	D02666		7			SM00001		9		YC059-YD152
0502	18		HA		1-10	29-34-11	D02666		7			SM00001		9		YD153-YL968, YN231-YN236, YN501-YR323, YR325-YR328
0503	18		HA		59-4	29-11-12	D02666		4			SP00010		S		YC051-YC055
0503	18		HA		59-6	29-11-12	D02666		4			SP00010		S		YC056-YC058
0503	18		HA		59-9	29-11-12	D02666		4			SP00010		S		YC059-YD152
0503	18		HA		61-1	29-11-12	D02666		4			SP00010		S		YD153-YD157
0503	18		HA		60-11	29-11-12	D02666		4			SP00010		S		YD158-YL963
0503	18		HA		60-10	29-11-12	D02666		4			SP00010		S		YL964-YL968, YR301
0503	18		HA		48-5	29-11-12	D02666		4			SP00010		S		YN231-YN236, YN501
0503	18		HA		60-0	29-11-12	D02666		4			SP00010		S		YR303-YR323, YR325-YR328
0504	10		CQ		57-2	29-11-12	D02666		1	10		D11428		D		YC051-YC055
0504	10		CQ		57-4	29-11-12	D02666		1	10		D11428		D		YC056-YC058
0504	10		CQ		57-7	29-11-12	D02666		1	10		D11428		D		YC059-YD152
0504	10		CQ		58-11	29-11-12	D02666		1	10		D11428		D		YD153-YD157
0504	10		CQ		58-9	29-11-12	D02666		1	10		D11428		D		YD158-YL963
0504	10		CQ		58-8	29-11-12	D02666		1	10		D11428		D		YL964-YL968, YR301
0504	10		CQ		47-6	29-11-12	D02666		1	10		D11428		D		YN231-YN235
0504	10		CQ		47-5	29-11-12	D02666		1	10		D11428		D		YN236, YN501
0504	10		CQ		57-10	29-11-12	D02666		1	10		D11428		D		YR303-YR323, YR325-YR328
0505	10		CQ		57-2	29-11-12	D02666		3	10		D11428		E		YC051-YC055
0505	10		CQ		57-4	29-11-12	D02666		3	10		D11428		E		YC056-YC058
0505	10		CQ		57-7	29-11-12	D02666		3	10		D11428		E		YC059-YD152
0505	10		CQ		58-11	29-11-12	D02666		3	10		D11428		E		YD153-YD157
0505	10		CQ		58-9	29-11-12	D02666		3	10		D11428		E		YD158-YL963
0505	10		CQ		58-8	29-11-12	D02666		3	10		D11428		E		YL964-YL968, YR301
0505	10		CQ		47-6	29-11-12	D02666		3	10		D11428		E		YN231-YN235
0505	10		CQ		47-5	29-11-12	D02666		3	10		D11428		E		YN236, YN501
0505	10		CQ		57-10	29-11-12	D02666		3	10		D11428		E		YR303-YR323, YR325-YR328
0506	10		CQ		57-2	29-11-12	D02666		6	10		D11428		F		YC051-YC055
0506	10		CQ		57-4	29-11-12	D02666		6	10		D11428		F		YC056-YC058
0506	10		CQ		57-7	29-11-12	D02666		6	10		D11428		F		YC059-YD152
0506	10		CQ		58-11	29-11-12	D02666		6	10		D11428		F		YD153-YD157
0506	10		CQ		58-9	29-11-12	D02666		6	10		D11428		F		YD158-YL963

WIRE LIST

D280A108

91-21-11

Section W5230

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W5230	286A5230				E/E BAY TO MWW-SYS B ELEC HYD PUMP (continued)												
0506	10		CQ		58-8	29-11-12		D02666		6	10		D11428		F		YL964-YL968, YR301
0506	10		CQ		47-6	29-11-12		D02666		6	10		D11428		F		YN231-YN235
0506	10		CQ		47-5	29-11-12		D02666		6	10		D11428		F		YN236, YN501
0506	10		CQ		57-10	29-11-12		D02666		6	10		D11428		F		YR303-YR323, YR325-YR328
0507	18		HA		2-0	29-34-11		D02690		B			SM00001		9		YC051-YC058
0507	18		HA		2-4	29-34-11		D02690		B			SM00001		9		YC059-YD152
0507	18		HA		3-5	29-34-11		D02690		B			SM00001		9		YD153-YL968, YN231-YN236, YN501-YR323, YR325-YR328
0508	18		HA		3-5	29-34-11		D02690		A			GD00322	DC..	E		YC051-YC058, YD153-YL968, YN231-YN236, YN501-YR323, YR325-YR328
0508	18		HA		3-4	29-34-11		D02690		A			GD00322	DC..	E		YC059-YD152
0509	18		HA		58-7	29-34-11		D43062P		G			SM00001		9		YC051-YC055
0509	18		HA		58-11	29-34-11		D43062P		G			SM00001		9		YC056-YC058
0509	18		HA		58-4	29-34-11		D43062P		G			SM00001		9		YC059-YD152
0509	18		HA		60-7	29-34-11		D43062P		G			SM00001		9		YD153-YD157
0509	18		HA		60-4	29-34-11		D43062P		G			SM00001		9		YD158-YL963
0509	18		HA		60-3	29-34-11		D43062P		G			SM00001		9		YL964-YL968, YR301
0509	18		HA		48-3	29-34-11		D43062P		G			SM00001		9		YN231-YN235
0509	18		HA		48-2	29-34-11		D43062P		G			SM00001		9		YN236, YN501
0509	18		HA		59-5	29-34-11		D43062P		G			SM00001		9		YR303-YR323, YR325-YR328
0510	12		CQ		6-0	49-41-11		D11428		A			D43084P		1		YC051-YL968, YN231-YN236, YN501-YR323, YR325-YR328
0511	12		CQ		6-0	49-41-11		D11428		B			D43084P		2		YC051-YL968, YN231-YN236, YN501-YR323, YR325-YR328
0512	12		CQ		6-0	49-41-11		D11428		C			D43084P		3		YC051-YL968, YN231-YN236, YN501-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W5230

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W5230	286A5230				E/E BAY TO MWW-SYS B ELEC HYD PUMP (continued)												
0513	18		PA		91-1	38-32-12	D43084P		4			D11718	5			YC051-YC055	
0513	18		PA		91-0	38-32-12	D43084P		4			D11718	5			YC056-YL968, YR301-YR323, YR325-YR328	
0513	18		PA		71-10	38-32-12	D43084P		4			D11718	5			YN231-YN236, YN501	
0514	18		PA		90-3	38-32-12	D43084P		5			D40152J	1			YC051-YC055	
0514	18		PA		90-2	38-32-12	D43084P		5			D40152J	1			YC056-YL968, YR301-YR323, YR325-YR328	
0514	18		PA		71-0	38-32-12	D43084P		5			D40152J	1			YN231-YN236, YN501	
0515	12		CQ		91-8	38-32-12	D11428		G			D11718	2			YC051-YC055	
0515	12		CQ		91-7	38-32-12	D11428		G			D11718	2			YC056-YL968, YR301-YR323, YR325-YR328	
0515	12		CQ		72-5	38-32-12	D11428		G			D11718	2			YN231-YN236, YN501	
0516	12		CQ		91-8	38-32-12	D11428		H			D11718	3			YC051-YC055	
0516	12		CQ		91-7	38-32-12	D11428		H			D11718	3			YC056-YL968, YR301-YR323, YR325-YR328	
0516	12		CQ		72-5	38-32-12	D11428		H			D11718	3			YN231-YN236, YN501	
0517	12		CQ		91-8	38-32-12	D11428		I			D11718	4			YC051-YC055	
0517	12		CQ		91-7	38-32-12	D11428		I			D11718	4			YC056-YL968, YR301-YR323, YR325-YR328	
0517	12		CQ		72-5	38-32-12	D11428		I			D11718	4			YN231-YN236, YN501	
0518	12		CQ		2-3	38-32-12	D11718		7			GD00074	ST..	E		YC051-YL968, YN231-YN236, YN501-YR323, YR325-YR328	
0519	20		CQ		2-1	38-32-12	D40152J		2			D11718	6			YC051-YL968, YN231-YN236, YN501-YR323, YR325-YR328	
6011	18		CQ		21-7	28-21-11	SP00326		9			SP00202		S		YC051-YD152	
6011	18		CQ		22-3	28-21-11	SP00326		9			SP00202		S		YD153-YD157	
6011	18		CQ		22-0	28-21-11	SP00326		9			SP00202		S		YD158-YL963	
6011	18		CQ		22-1	28-21-11	SP00326		9			SP00202		S		YL964-YL968, YR301	
6011	18		CQ		21-5	28-21-11	SP00326		9			SP00202		S		YN231-YN236, YN501	

WIRE LIST

D280A108

91-21-11

Section W5230

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description	Diagram	From				To				Effectivity	
Wire No.	GA	CO	TY		FT-IN		Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W5230	286A5230				E/E BAY TO MWW-SYS B ELEC HYD PUMP (continued)											
6011	18		CQ		21-3	28-21-11	SP00326			9		SP00202		S		YR303-YR323, YR325-YR328
YAAF					0-0	29-11-12	GD00012	ST..		1		GD02304	ST..	GW		YC051-YL968, YN231-YN236, YN501-YR323, YR325-YR328
W5234	286A5234				DISC AL0720A TO E1-3											
0501	20		PA		77-9	32-41-11	D43010P			1		D46024J		4		YC051-YL999, YR301-YR328
0501	20		PA		67-10	32-41-11	D43010P			1		D46024J		4		YN231-YN501
0511	22		PA		77-9	31-31-15	D46024J			1		D43010P		18		YC051-YL999, YR301-YR328
0511	22		PA		67-10	31-31-15	D46024J			1		D43010P		18		YN231-YN501
0591	22		PA		77-9	32-41-11	D43010P			2		D46024J		11		YC051-YL999, YR301-YR328
0591	22		PA		67-10	32-41-11	D43010P			2		D46024J		11		YN231-YN501
0592	22		PA		21-3	32-41-11	D46024J			12		GD05108	DC..	1		YC051-YL999, YR301-YR328
0592	22		PA		21-1	32-41-11	D46024J			12		GD05108	DC..	1		YN231-YN501
2203B	22		PB	KC	77-9	32-42-11	D43010P			4		D46024J		14		YC051-YL999, YR301-YR328
2203B	22		PB	KC	67-10	32-42-11	D43010P			4		D46024J		14		YN231-YN501
2203R	22		PB	KC	0-0	32-42-11	D43010P			3		D46024J		13		ALL
2204B	22		PB	KD	77-9	32-42-11	D43010P			6		D46024J		16		YC051-YL999, YR301-YR328
2204B	22		PB	KD	67-10	32-42-11	D43010P			6		D46024J		16		YN231-YN501
2204R	22		PB	KD	0-0	32-42-11	D43010P			5		D46024J		15		ALL
2211B	22		X2	KK	77-9	32-41-11	D43010P			8		D46024J		18		YC051-YL999, YR301-YR328
2211B	22		X2	KK	67-10	32-41-11	D43010P			8		D46024J		18		YN231-YN501
2211R	22		X2	KK	0-0	32-41-11	D43010P			7		D46024J		17		ALL
2211Z				KK	0-0	32-41-11	D43010P			17		D46024J		19		ALL
2221B	22		PB	KV	77-9	32-64-12	D43010P			12		D46024J		8		YC051-YL999, YR301-YR328
2221B	22		PB	KV	67-10	32-64-12	D43010P			12		D46024J		8		YN231-YN501
2221R	22		PB	KV	0-0	32-64-12	D43010P			11		D46024J		7		ALL
2222B	22		PB	KW	77-9	32-64-12	D43010P			10		D46024J		6		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W5230

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5234	286A5234			DISC AL0720A TO E1-3 (continued)											
2222B	22	PB	KW		67-10	32-64-12	D43010P	10			D46024J	6			YN231-YN501
2222R	22	PB	KW		0-0	32-64-12	D43010P	9			D46024J	5			ALL
2233B	22	PB	LH		77-9	32-31-12	D43010P	15			D46024J	10			YC051-YL999, YR301-YR328 YN231-YN501
2233B	22	PB	LH		67-10	32-31-12	D43010P	15			D46024J	10			ALL
2233R	22	PB	LH		0-0	32-31-12	D43010P	13			D46024J	9			ALL

WIRE LIST

D280A108

91-21-11

Section W5230

Page 6 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5248	286A5248				E/E BAY TO FWD AND AFT CARGO AREA										
0001	20		PA		2-6	31-35-05	D39921		1		GD00068	ST..	1		YL963-YL999, YR301-YR328
0001	20		PA		3-11	31-35-05	D39921		1		GD00068	ST..	1		YN236-YN501
0002	20		PA		7-8	33-36-11	L00194	PWR	C		SM00010		S		YC051-YC055
0002	20		PA		12-4	33-36-11	L00194	PWR	C		SM00010		S		YC056-YL999, YR301-YR328
0002	20		PA		8-1	33-36-11	L00194	PWR	C		SM00010		S		YN231-YN501
0004	20		PA		12-8	33-36-11	D11764		1		SM00010		S		YC051-YC055
0004	20		PA		9-7	33-36-11	D11764		1		SM00010		S		YC056-YL999, YR301-YR328
0004	20		PA		6-3	33-36-11	D11764		1		SM00004		S		YN231-YN501
0006	20		PA		7-9	33-36-11	D11766		1		SM00006		S		YN231-YN501
0007	20		PA		1-8	33-36-11	S00067		2	C	GD00084	DC..	1A		YC051-YL999, YR301-YR328
0007	20		PA		1-9	33-36-11	S00067		2	C	GD00084	DC..	1A		YN231-YN501
0008	20		PA		15-9	33-36-11	D11758		1		SM00008		S		YC051-YC055
0008	20		PA		5-3	33-36-11	D11758		1		SM00008		S		YC056-YL999, YR301-YR328
0008	20		PA		5-5	33-36-11	D11758		1		SM00008		S		YN231-YN501
0010	20		PA		2-3	33-36-11	D11760		1		SM00010		S		YC051-YC055
0010	20		PA		7-1	33-36-11	D11760		1		SM00010		S		YC056-YL999, YR301-YR328
0010	20		PA		1-10	33-36-11	D11760		1		SM00010		S		YN231-YN501
0011	20		PA		17-0	33-36-11	SM00008			S	SM00010		S		YC051-YC055
0011	20		PA		2-2	33-36-11	SM00008			S	SM00010		S		YC056-YL999, YR301-YR328
0011	20		PA		6-11	33-36-11	SM00008			S	SM00010		S		YN231-YN501
0012	20		PA		2-1	33-36-11	L00194	GND	C		GD00432	AC..	1		YC051-YC055
0012	20		PA		2-4	33-36-11	L00194	GND	C		GD00432	AC..	1		YC056-YL999, YR301-YR328
0012	20		PA		2-2	33-36-11	L00194	GND	C		GD00432	AC..	1		YN231-YN501
0014	20		PA		2-2	33-36-11	D11764		2		GD00086	AC..	1		YC051-YL999, YR301-YR328
0014	20		PA		1-8	33-36-11	D11764		2		GD00086	AC..	1		YN231-YN501
0016	20		PA		1-11	33-36-11	D11766		2		GD01370	AC..	1		YN231-YN501
0017	20		PA		26-8	33-36-11	D40584P	A04			S00067		1	C	YC051-YC055
0017	20		PA		26-9	33-36-11	D40584P	A04			S00067		1	C	YC056-YR328
0018	20		PA		1-11	33-36-11	D11758		2		GD00428	AC..	1		ALL

WIRE LIST

D280A108

91-21-11

Section W5240

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W5248	286A5248	E/E BAY TO FWD AND AFT CARGO AREA (continued)			
0020	20 PA	2-8 33-36-11	D11760 2	GD00430 AC.. 1	YC051-YL999, YR301-YR328
0020	20 PA	1-10 33-36-11	D11760 2	GD00430 AC.. 1	YN231-YN501
0024	20 PA	20-2 33-36-11	D40584P A06	SM00006 S	YC051-YL999, YR301-YR328
0024	20 PA	16-6 33-36-11	D40584P A06	SM00004 S	YN231-YN501
0026	20 PA	8-2 33-36-11	SM00009 S	D11996 1	YC051-YC055
0026	20 PA	8-4 33-36-11	SM00009 S	D11996 1	YC056-YL999, YR301-YR328
0028	20 PA	0-10 33-36-11	D40584P B06	SM00008 S	YC051-YC055
0028	20 PA	11-5 33-36-11	D40584P B06	SM00008 S	YC056-YR328
0034	20 PA	2-3 33-36-11	SM00004 S	SM00006 S	YN231-YN501
0036	20 PA	2-4 33-36-11	D11996 2	GD08044 AC.. 1	YC051-YL999, YR301-YR328
0038	20 PA	8-1 33-36-11	D11768 1	SM00006 S	YN231-YN501
0039	20 PA	8-5 33-36-11	SM00009 S	SM00006 S	YC051-YC055
0039	20 PA	8-4 33-36-11	SM00009 S	SM00006 S	YC056-YL999, YR301-YR328
0044	20 PA	7-11 33-36-11	SM00009 S	D11994 1	YC051-YC055
0044	20 PA	8-1 33-36-11	SM00009 S	D11994 1	YC056-YL999, YR301-YR328
0046	20 PA	34-0 52-71-12	D40584P A10	D40500J 23	YC051-YC055
0046	20 PA	34-1 52-71-12	D40584P A10	D40500J 23	YC056-YL999, YR301-YR328
0046	20 PA	24-6 52-71-12	D40584P A10	D40500J 23	YN231-YN501
0048	20 PA	2-7 33-36-11	D11768 2	GD00088 AC.. 1	YN231-YN501
0054	20 PA	2-8 33-36-11	D11994 2	GD08042 AC.. 1	YC051-YL999, YR301-YR328
0056	20 PA	26-1 52-71-12	D40584P B10	S00960 NO C	YC051-YC055
0056	20 PA	26-2 52-71-12	D40584P B10	S00960 NO C	YC056-YL952
0056	20 PA	26-11 52-71-12	D40584P B10	SP01256 S	YL953-YL999, YR301-YR328
0056	20 PA	25-11 52-71-12	D40584P B10	S00960 NO C	YN231-YN233
0056	20 PA	26-10 52-71-12	D40584P B10	SP01256 S	YN234-YN501
0070	20 PA	7-5 33-36-11	D12170 1	SM00006 S	YC051-YC055
0070	20 PA	7-7 33-36-11	D12170 1	SM00006 S	YC056-YL999, YR301-YR328
0072	20 PA	9-9 33-36-11	D12172 1	SM00006 S	YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5240

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5248	286A5248			E/E BAY TO FWD AND AFT CARGO AREA (continued)											
0072	20		PA		9-11	33-36-11	D12172		1		SM00006		S		YC056-YL999, YR301-YR328
0080	20		PA		1-10	33-36-11	D12170		2		GD08046	AC..	1		YC051-YL999, YR301-YR328
0082	20		PA		2-3	33-36-11	D12172		2		GD08048	AC..	1		YC051-YL999, YR301-YR328
0156	20		PA		2-7	52-71-12	S00960		C	C	GD00084	DC..	1A		YC051-YL952
0156	20		PA		3-4	52-71-12	SP01258			S	GD00084	DC..	1A		YL953-YL999, YR301-YR328
0156	20		PA		2-3	52-71-12	S00960		C	C	GD00084	DC..	1A		YN231-YN233
0156	20		PA		3-2	52-71-12	SP01258			S	GD00084	DC..	1A		YN234-YN501
0287	20		PA		34-0	33-36-12	D40584P		B04		D40500J		4		YC051-YC055
0287	20		PA		34-1	33-36-12	D40584P		B04		D40500J		4		YC056-YL999, YR301-YR328
0287	20		PA		24-6	33-36-12	D40584P		B04		D40500J		4		YN231-YN501
0288	20		PA		34-0	33-36-12	D40584P		A07		D40500J		5		YC051-YC055
0288	20		PA		34-1	33-36-12	D40584P		A07		D40500J		5		YC056-YL999, YR301-YR328
0288	20		PA		24-6	33-36-12	D40584P		A07		D40500J		5		YN231-YN501
0384	20		PA		34-0	33-36-12	D40584P		B07		D40500J		6		YC051-YC055
0384	20		PA		34-1	33-36-12	D40584P		B07		D40500J		6		YC056-YL999, YR301-YR328
0384	20		PA		24-6	33-36-12	D40584P		B07		D40500J		6		YN231-YN501
0499	20		PA		34-0	SPARE	D40584P		A01		D40500J		1		YC051-YC055
0499	20		PA		34-1	SPARE	D40584P		A01		D40500J		1		YC056-YL999, YR301-YR328
0499	20		PA		24-6	SPARE	D40584P		A01		D40500J		1		YN231-YN501
0500	20		PA		34-0	SPARE	D40584P		B01		D40500J		3		YC051-YC055
0500	20		PA		34-1	SPARE	D40584P		B01		D40500J		3		YC056-YL999, YR301-YR328
0500	20		PA		24-6	SPARE	D40584P		B01		D40500J		3		YN231-YN501
1301R	20		X5	EN	32-6	26-12-11	D40586P		A10		D40500J		37		YC051-YC055
1301R	20		X5	EN	32-9	26-12-11	D40586P		A10		D40500J		37		YC056-YL999, YR301-YR328
1301R	20		X5	EN	23-1	26-12-11	D40586P		A10		D40500J		37		YN231-YN501
1301Z				EN	0-0	26-12-11	D40586P		DED		D40500J	DED			ALL
1302R	20		X5	EP	32-6	26-12-11	D40586P		B10		D40500J		38		YC051-YC055
1302R	20		X5	EP	32-9	26-12-11	D40586P		B10		D40500J		38		YC056-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W5240

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5248		286A5248			E/E BAY TO FWD AND AFT CARGO AREA (continued)											
1302R		20		X5	EP	23-1	26-12-11	D40586P	B10			D40500J	38			YN231-YN501
1302Z					EP	0-0	26-12-11	D40586P	DED			D40500J	DED			ALL
2001B		20		X2	AA	34-2	31-35-05	D39921	32			D40130P	B15			YL963-YL999, YR301-YR328
2001B		20		X2	AA	24-4	31-35-05	D39921	32			D40130P	B15			YN236-YN501
2001R		20		X2	AA	0-0	31-35-05	D39921	33			D40130P	A15			YL963-YL999, YN236-YR328
2001Z					AA	0-0	31-35-05	D39921	S/R			D40130P	PERG	1F		YL963-YL999, YN236-YR328
2409B		20		PB	OI	34-0	52-71-11	D40584P	B03			D40500J	11			YC051-YC055
2409B		20		PB	OI	34-1	52-71-11	D40584P	B03			D40500J	11			YC056-YL999, YR301-YR328
2409B		20		PB	OI	24-6	52-71-11	D40584P	B03			D40500J	11			YN231-YN501
2409R		20		PB	OI	0-0	52-71-11	D40584P	A03			D40500J	26			ALL
2444B		20		PB	PT	34-0	52-71-11	D40584P	B05			D40500J	10			YC051-YC055
2444B		20		PB	PT	34-1	52-71-11	D40584P	B05			D40500J	10			YC056-YL999, YR301-YR328
2444B		20		PB	PT	24-6	52-71-11	D40584P	B05			D40500J	10			YN231-YN501
2444R		20		PB	PT	0-0	52-71-11	D40584P	A05			D40500J	25			ALL
5509		20		PA		32-6	30-71-11	D40586P	B02			D40500J	9			YC051-YC055
5509		20		PA		32-9	30-71-11	D40586P	B02			D40500J	9			YC056-YL999, YR301-YR328
5509		20		PA		23-1	30-71-11	D40586P	B02			D40500J	9			YN231-YN501
5513		20		PA		32-6	30-71-11	D40586P	B03			D40500J	13			YC051-YC055
5513		20		PA		32-9	30-71-11	D40586P	B03			D40500J	13			YC056-YL999, YR301-YR328
5513		20		PA		23-1	30-71-11	D40586P	B03			D40500J	13			YN231-YN501
5514		20		PA		32-6	30-71-11	D40586P	B01			D40500J	14			YC051-YC055
5514		20		PA		32-9	30-71-11	D40586P	B01			D40500J	14			YC056-YL999, YR301-YR328
5514		20		PA		23-1	30-71-11	D40586P	B01			D40500J	14			YN231-YN501
5524		20		PA		32-6	30-71-11	D40586P	A03			D40500J	24			YC051-YC055
5524		20		PA		32-9	30-71-11	D40586P	A03			D40500J	24			YC056-YL999, YR301-YR328
5524		20		PA		23-1	30-71-11	D40586P	A03			D40500J	24			YN231-YN501
A-A						0-0	52-71-12	SP01256		S		S00960	NO	C		YL953-YL999, YN234-YR328
A-B						0-0	52-71-12	SP01258		S		S00960	C	C		YL953-YL999, YN234-YR328

WIRE LIST

D280A108

91-21-11

Section W5240

Page 4 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5257	286A5257			FLIGHT RECORDER E3-2 SHELF TO CONTROL POSITION SENSORS											
0001	22		PA		22-7	31-35-03	D43257P		B06		SP00779		S		YN236-YR328
2001B	22		PB	AB	31-9	31-31-14	D43257P		A05		D00815	1			ALL
2001R	22		PB	AB	0-0	31-31-14	D43257P		A04		D00815	5			ALL
2002B	22		PB	AC	30-8	31-31-14	D43257P		A07		D00817	1			ALL
2002R	22		PB	AC	0-0	31-31-14	D43257P		A06		D00817	5			ALL
2003B	22		PB	AE	26-8	31-31-14	D43257P		B02		D00819	1			YC051-YC055
2003B	22		PB	AE	26-7	31-31-14	D43257P		B02		D00819	1			YC056-YR328
2003R	22		PB	AE	0-0	31-31-14	D43257P		B01		D00819	2			ALL
3001B	22		PC	AA	31-9	31-31-14	D43257P		A01		D00815	2			ALL
3001R	22		PC	AA	0-0	31-31-14	D43257P		A02		D00815	3			ALL
3001Y	22		PC	AA	0-0	31-31-14	D43257P		A03		D00815	4			ALL
3002B	22		PC	AD	30-8	31-31-14	D43257P		A09		D00817	2			ALL
3002R	22		PC	AD	0-0	31-31-14	D43257P		A08		D00817	3			ALL
3002Y	22		PC	AD	0-0	31-31-14	D43257P		A10		D00817	4			ALL
3003B	22		PC	AF	26-8	31-31-14	D43257P		B04		D00819	5			YC051-YC055
3003B	22		PC	AF	26-7	31-31-14	D43257P		B04		D00819	5			YC056-YR328
3003R	22		PC	AF	0-0	31-31-14	D43257P		B03		D00819	4			ALL
3003Y	22		PC	AF	0-0	31-31-14	D43257P		B05		D00819	3			ALL

WIRE LIST

D280A108

91-21-11

Section W5250

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W5273	286A5273				ADF ANTENNA -1											
0001	20		PA		1-9	34-57-11		D03663			AB	GD00083	ST..	E		ALL
0003	20		PA		1-9	34-57-11		D03663	14			GD00083	ST..	E		ALL
8991B	24		V2	1A	67-3	34-57-11		D03663	2			D42163P	A02			YC051-YC055
8991B	24		V2	1A	65-11	34-57-11		D03663	2			D42163P	A02			YC056-YL999, YR301-YR328
8991B	24		V2	1A	55-10	34-57-11		D03663	2			D42163P	A02			YN231-YN501
8991G	24		V2	1B	0-0	34-57-11		D03663	5			D42163P	A04			ALL
8991K	24		V2	1C	0-0	34-57-11		D03663	8			D42163P	A06			ALL
8991N	22		V2	1D	0-0	34-57-11		D03663	11			D42163P	A08			ALL
8991O	22		V2	1D	0-0	34-57-11		D03663	10			D42163P	A07			ALL
8991R	24		V2	1A	0-0	34-57-11		D03663	1			D42163P	A01			ALL
8991V	24		V2	1C	0-0	34-57-11		D03663	7			D42163P	A05			ALL
8991W	20		V2	1E	0-0	34-57-11		D03663	12			D42163P	A09			ALL
8991Y	24		V2	1B	0-0	34-57-11		D03663	4			D42163P	A03			ALL
8991Z				1E	0-0	34-57-11		GD00083	ST..	E		D42163P	PERG	1F		ALL
8991ZA				1A	0-0	34-57-11		D03663			AB	D42163P	PERG	1F		ALL
8991ZB				1B	0-0	34-57-11		D03663			AB	D42163P	PERG	1F		ALL
8991ZC				1C	0-0	34-57-11		D03663			AB	D42163P	PERG	1F		ALL
W5275	286A5275				ADF ANTENNA -2											
0001	20		PA		1-9	34-57-21		D03665			AB	GD00085	ST..	=		YC051-YL956, YL958-YR328
0001	20		PA		1-9	34-57-21		D03665			AB	GD00085	ST..	E		YL957
0003	20		PA		1-9	34-57-21		D03665	14			GD00085	ST..	=		YC051-YL956, YL958-YR328
0003	20		PA		1-9	34-57-21		D03665	14			GD00085	ST..	E		YL957
8991B	24		V2	1A	66-4	34-57-21		D03665	2			D42165P	A02			YC051-YL999, YR301-YR328
8991B	24		V2	1A	56-4	34-57-21		D03665	2			D42165P	A02			YN231-YN501
8991G	24		V2	1B	0-0	34-57-21		D03665	5			D42165P	A04			ALL
8991K	24		V2	1C	0-0	34-57-21		D03665	8			D42165P	A06			ALL
8991N	22		V2	1D	0-0	34-57-21		D03665	11			D42165P	A08			ALL
8991O	22		V2	1D	0-0	34-57-21		D03665	10			D42165P	A07			ALL
8991R	24		V2	1A	0-0	34-57-21		D03665	1			D42165P	A01			ALL
8991V	24		V2	1C	0-0	34-57-21		D03665	7			D42165P	A05			ALL
8991W	20		V2	1E	0-0	34-57-21		D03665	12			D42165P	A09			ALL
8991Y	24		V2	1B	0-0	34-57-21		D03665	4			D42165P	A03			ALL
8991Z				1E	0-0	34-57-21		GD00085	ST..	=		D42165P	PERG	1F		YC051-YL956, YL958-YR328

WIRE LIST

D280A108

91-21-11

Section W5270

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5275	286A5275			ADF ANTENNA -2 (continued)											
8991Z				1E	0-0	34-57-21	GD00085	ST..	E		D42165P	PERG	1F		YL957
8991ZA				1A	0-0	34-57-21	D03665			AB	D42165P	PERG	1F		ALL
8991ZB				1B	0-0	34-57-21	D03665			AB	D42165P	PERG	1F		ALL
8991ZC				1C	0-0	34-57-21	D03665			AB	D42165P	PERG	1F		ALL

WIRE LIST

D280A108

91-21-11

Section W5270

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5293	286A5293			RADIO ALTM XMTR ANT -1 (R/T) STA 450 TO E3-1											
001CO				AA	0-0	34-33-11	D03671		= C1		D03667B		= C71		ALL
001CX		0H		AA	15-1	34-33-11	D03671		= A1		D03667B		71		ALL
W5295	286A5295			RADIO ALTM RCVR ANT -1 (R/T) STA 430 TO E3-1											
001CO				AA	0-0	34-33-11	D03675		= C1		D03667A		= C71		ALL
001CX		0H		AA	15-1	34-33-11	D03675		= A1		D03667A		71		ALL
W5297	286A5297			RADIO ALTM XMTR ANT -2 (R/T) STA 390 TO E3-2											
001CO				AA	0-0	34-33-21	D03673		= C1		D03669B		= C71		YC051-YN236, YN501-YR328
001CX		0H		AA	15-1	34-33-21	D03673		= A1		D03669B		71		YC051-YN236, YN501-YR328
W5299	286A5299			RADIO ALTM RCVR ANT -2 (R/T) STA 410 TO E3-2											
001CO				AA	0-0	34-33-21	D03677		= C1		D03669A		= C71		ALL
001CX		0H		AA	15-1	34-33-21	D03677		= A1		D03669A		71		ALL

WIRE LIST

D280A108

91-21-11

Section W5290

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5301	286A5301			MACH TRIM SERVO, E1-1 TO STA 1156											
0011	20		PA		2-11	22-18-11	D00545		11		GD00479	DC..	E		YC051-YC052
0013	20		PA		130-5	22-18-11	D04425P		B03		D00545		13		YC051-YC052
0013	20		PA		116-1	22-18-11	D04425P		B03		D43393P		13		YC053-YC055
0013	20		PA		116-8	22-18-11	D04425P		B03		D43393P		13		YC056-YL953
0013	20		PA		117-1	22-18-11	D04425P		B03		D43393P		13		YL954-YL999, YR301-YR328
0013	20		PA		97-4	22-18-11	D04425P		B03		D43393P		13		YN231-YN501
0014	20		PA		2-11	22-18-11	D00545		14		GD00479	DC..	E		YC051-YC052
0015	22		PA		130-5	SPARE	D04425P		A05		D00545		15		YC051-YC052
0015	22		PA		116-1	SPARE	D04425P		A05		D43393P		15		YC053-YC055
0015	22		PA		116-8	SPARE	D04425P		A05		D43393P		15		YC056-YL953
0015	22		PA		117-1	SPARE	D04425P		A05		D43393P		15		YL954-YL999, YR301-YR328
0015	22		PA		97-4	SPARE	D04425P		A05		D43393P		15		YN231-YN501
0017	22		PA		130-5	SPARE	D04425P		A07		D00545		17		YC051-YC052
0017	22		PA		116-1	SPARE	D04425P		A07		D43393P		17		YC053-YC055
0017	22		PA		116-8	SPARE	D04425P		A07		D43393P		17		YC056-YL953
0017	22		PA		117-1	SPARE	D04425P		A07		D43393P		17		YL954-YL999, YR301-YR328
0017	22		PA		97-4	SPARE	D04425P		A07		D43393P		17		YN231-YN501
0019	22		PA		130-5	SPARE	D04425P		A09		D00545		19		YC051-YC052
0019	22		PA		116-1	SPARE	D04425P		A09		D43393P		19		YC053-YC055
0019	22		PA		116-8	SPARE	D04425P		A09		D43393P		19		YC056-YL953
0019	22		PA		117-1	SPARE	D04425P		A09		D43393P		19		YL954-YL999, YR301-YR328
0019	22		PA		97-4	SPARE	D04425P		A09		D43393P		19		YN231-YN501
0021	22		PA		130-5	SPARE	D04425P		B01		D00545		21		YC051-YC052
0021	22		PA		116-1	SPARE	D04425P		B01		D43393P		21		YC053-YC055
0021	22		PA		116-8	SPARE	D04425P		B01		D43393P		21		YC056-YL953
0021	22		PA		117-1	SPARE	D04425P		B01		D43393P		21		YL954-YL999, YR301-YR328
0021	22		PA		97-4	SPARE	D04425P		B01		D43393P		21		YN231-YN501
2001B	22		PB	AA	130-5	22-18-11	D04425P		A01		D00545		1		YC051-YC052
2001B	22		PB	AA	116-1	22-18-11	D04425P		A01		D43393P		2		YC053-YC055
2001B	22		PB	AA	116-8	22-18-11	D04425P		A01		D43393P		2		YC056-YL953
2001B	22		PB	AA	117-1	22-18-11	D04425P		A01		D43393P		2		YL954-YL999, YR301-YR328
2001B	22		PB	AA	97-4	22-18-11	D04425P		A01		D43393P		2		YN231-YN501
2001R	22		PB	AA	0-0	22-18-11	D04425P		A02		D00545		2		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W5300

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5301		286A5301			MACH TRIM SERVO, E1-1 TO STA 1156 (continued)											
2001R		22		PB	AA	0-0	22-18-11	D04425P	A02			D43393P	1			YC053-YR328
2006B		22		PB	AF	130-5	22-18-11	D04425P	A03			D00545	3			YC051-YC052
2006B		22		PB	AF	116-1	22-18-11	D04425P	A03			D43393P	6			YC053-YC055
2006B		22		PB	AF	116-8	22-18-11	D04425P	A03			D43393P	6			YC056-YL953
2006B		22		PB	AF	117-1	22-18-11	D04425P	A03			D43393P	6			YL954-YL999, YR301-YR328
2006B		22		PB	AF	97-4	22-18-11	D04425P	A03			D43393P	6			YN231-YN501
2006R		22		PB	AF	0-0	22-18-11	D04425P	A04			D00545	6			YC051-YC052
2006R		22		PB	AF	0-0	22-18-11	D04425P	A04			D43393P	5			YC053-YR328
2007B		22		PB	G	116-1	SPARE	D04425P	B10			D43393P	10			YC053-YC055
2007B		22		PB	G	116-8	SPARE	D04425P	B10			D43393P	10			YC056-YL953
2007B		22		PB	G	117-1	SPARE	D04425P	B10			D43393P	10			YL954-YL999, YR301-YR328
2007B		22		PB	G	97-4	SPARE	D04425P	B10			D43393P	10			YN231-YN501
2007R		22		PB	G	0-0	SPARE	D04425P	B09			D43393P	9			YC053-YR328
2024B		22		PB	AY	130-5	22-18-11	D04425P	B07			D00545	23			YC051-YC052
2024B		22		PB	AY	116-1	22-18-11	D04425P	B07			D43393P	4			YC053-YC055
2024B		22		PB	AY	116-8	22-18-11	D04425P	B07			D43393P	4			YC056-YL953
2024B		22		PB	AY	117-1	22-18-11	D04425P	B07			D43393P	4			YL954-YL999, YR301-YR328
2024B		22		PB	AY	97-4	22-18-11	D04425P	B07			D43393P	4			YN231-YN501
2024R		22		PB	AY	0-0	22-18-11	D04425P	B08			D00545	24			YC051-YC052
2024R		22		PB	AY	0-0	22-18-11	D04425P	B08			D43393P	3			YC053-YR328
2026B		22		PB	BA	130-5	22-18-11	D04425P	B05			D00545	25			YC051-YC052
2026B		22		PB	BA	116-1	22-18-11	D04425P	B05			D43393P	8			YC053-YC055
2026B		22		PB	BA	116-8	22-18-11	D04425P	B05			D43393P	8			YC056-YL953
2026B		22		PB	BA	117-1	22-18-11	D04425P	B05			D43393P	8			YL954-YL999, YR301-YR328
2026B		22		PB	BA	97-4	22-18-11	D04425P	B05			D43393P	8			YN231-YN501
2026R		22		PB	BA	0-0	22-18-11	D04425P	B06			D00545	26			YC051-YC052
2026R		22		PB	BA	0-0	22-18-11	D04425P	B06			D43393P	7			YC053-YR328
W5303		286A5303			VIDEO - AB0340B TO EE BAY AND TB01806 TERMINAL TRACK - AUDIO & PA											
0001		22		CQ		28-4	23-32-12	D45231P	21			TB1806Y	B001	1A		YC051-YD157
0001		22		CQ		28-4	23-32-14	D45231P	21			TB1806Y	B001	1A		YD158-YD170
0001		22		PA		28-8	23-32-14	TB1806Y	B001	1A		D45231P	21			YL951-YN260
0002		22		PA		25-11	23-32-12	D45231P	1			D45279P	B03			YC051-YD170
0002		20		PA		6-4	23-34-01	D40173P	A03			D12165J	1			YL951-YN260
0002		20		PA		23-11	44-21-26	D45920P	40			D12165J	1			YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W5300

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5303	286A5303			VIDEO - AB0340B TO EE BAY AND TB01806 TERMINAL TRACK - AUDIO & PA (continued)											
0003	22		PA		27-6	23-32-12	D45231P	28			D45227P	1			YC051-YD157
0003	22		PA		25-11	23-32-12	D45231P	28			D45279P	B06			YD158-YD170
0003	22		PA		27-11	23-32-12	D45227P	1			D45231P	28			YL951-YN260
0004	22		PA		27-6	23-32-12	D45231P	29			D45227P	2			YC051-YD157
0005	22		PA		27-6	23-32-12	D45231P	30			D45227P	3			YC051-YD157
0005	22		PA		27-11	23-32-12	D45227P	13			D45231P	30			YL951-YN260
0006	18		PA		28-4	23-32-12	D45231P	36	18		TB1806V	A013	1		YC051-YD157
0007	20		PA		28-4	23-32-12	D45231P	37			TB1806X	B006	1A		YC051-YD157
0008	22		PA		27-6	23-32-12	D45231P	38			D45227P	14			YC051-YD157
0008	22		PA		27-6	23-32-14	D45231P	38			D45227P	14			YD158-YD170
0008	22		PA		27-11	23-32-14	D45231P	38			D45227P	14			YL951-YN260
0009	22		PA		27-6	23-32-12	D45231P	34			D45227P	15			YC051-YD157
0009	22		PA		27-6	23-32-14	D45231P	34			D45227P	15			YD158-YD170
0009	22		PA		27-11	23-32-14	D45231P	34			D45227P	15			YL951-YN260
0010	22		PA		27-6	23-32-12	D45231P	35			D45227P	16			YC051-YD157
0010	22		PA		27-6	23-32-14	D45231P	35			D45227P	16			YD158-YD170
0010	22		PA		27-11	23-32-14	D45231P	35			D45227P	16			YL951-YN260
0011	22		PA		27-6	23-32-12	D45231P	20			D45227P	6			YC051-YD157
0011	22		PA		27-6	23-32-14	D45231P	20			D45227P	6			YD158-YD170
0011	22		PA		27-11	23-32-14	D45231P	20			D45227P	6			YL951-YN260
0012	22		PA		25-11	SPARE	D45231P	36			D45279P	A20			YD158-YD170
0013	22		PA		25-11	SPARE	D45231P	37			D45279P	B20			YD158-YD170
0016	22		PA		27-6	23-32-14	D45231P	46			D45227P	3			YD158-YD170
0016	22		PA		27-11	23-32-14	D45231P	46			D45227P	3			YL951-YN260
0018	22		PA		27-6	23-32-14	D45231P	45			D45227P	2			YD158-YD170
0018	22		PA		27-11	23-32-14	D45231P	45			D45227P	2			YL951-YN260
0019	22		PA		27-11	23-34-01	D45231P	43			D45227P	37			YL951-YN260
0024	22		PA		33-0	23-34-01	D12213P	39			D12163J	21			YL951-YN260
0024	22		PA		23-11	44-21-26	D45920P	39			D12163J	21			YN501-YR328
0038	22		PA		6-4	23-34-01	D40173P	B13			D12165J	2			YL951-YN260
2501B	22		X2	AA	25-11	23-32-12	D45231P	6			D45279P	B01			YC051-YD170
2501B	22		X2	AA	33-0	23-34-01	D12213P	6			D12163J	2			YL951-YN260
2501B	22		X2	AA	23-11	44-21-26	D45920P	42			D12163J	2			YN501-YR328
2501R	22		X2	AA	0-0	23-32-12	D45231P	5			D45279P	A01			YC051-YD170
2501R	22		X2	AA	0-0	23-34-01	D12213P	5			D12163J	1			YL951-YN260
2501R	22		X2	AA	0-0	44-21-26	D45920P	41			D12163J	1			YN501-YR328
2501Z				AA	0-0	23-32-12	D45231P			AA	D45279P			AB	YC051-YD170
2501Z				AA	0-0	23-34-01	D12213P	PERB			D12163J	PERS	1A		YL951-YN260
2501Z				AA	0-0	44-21-26	D45920P	PERB			D12163J	PERS	1A		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W5300

Page 3

Nov 12/2012

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity	
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W5303	286A5303			VIDEO - AB0340B TO EE BAY AND TB01806 TERMINAL TRACK - AUDIO & PA (continued)											
2502B	22	X2	AB	25-11	23-32-12	D45231P		8			D45279P	B02			YC051-YD170
2502B	22	X2	AB	33-0	23-34-01	D12213P		8			D12163J	4			YL951-YN260
2502B	22	X2	AB	23-11	44-21-26	D45920P		44			D12163J	4			YN501-YR328
2502R	22	X2	AB	0-0	23-32-12	D45231P		7			D45279P	A02			YC051-YD170
2502R	22	X2	AB	0-0	23-34-01	D12213P		7			D12163J	3			YL951-YN260
2502R	22	X2	AB	0-0	44-21-26	D45920P		43			D12163J	3			YN501-YR328
2502Z			AB	0-0	23-32-12	D45231P				AA	D45279P			AB	YC051-YD170
2502Z			AB	0-0	23-34-01	D12213P			PERB		D12163J	PERS	1A		YL951-YN260
2502Z			AB	0-0	44-21-26	D45920P			PERB		D12163J	PERS	1A		YN501-YR328
2503B	22	X2	AC	25-11	23-32-12	D45231P		11			D45279P	B04			YC051-YD170
2503B	22	X2	AC	33-0	23-34-01	D12213P		10			D12163J	6			YL951-YN260
2503B	22	X2	AC	23-11	44-21-26	D45920P		50			D12163J	6			YN501-YR328
2503R	22	X2	AC	0-0	23-32-12	D45231P		10			D45279P	A04			YC051-YD170
2503R	22	X2	AC	0-0	23-34-01	D12213P		9			D12163J	5			YL951-YN260
2503R	22	X2	AC	0-0	44-21-26	D45920P		49			D12163J	5			YN501-YR328
2503Z			AC	0-0	23-32-12	D45231P				AC	D45279P			AD	YC051-YD170
2503Z			AC	0-0	23-34-01	D12213P			PERB		D12163J	PERS	1A		YL951-YN260
2503Z			AC	0-0	44-21-26	D45920P			PERB		D12163J	PERS	1A		YN501-YR328
2504B	22	X2	AD	25-11	23-32-12	D45231P		13			D45279P	B05			YC051-YD170
2504B	22	X2	AD	33-0	23-34-01	D12213P		13			D12163J	10			YL951-YN260
2504B	22	X2	AD	23-11	44-21-26	D45920P		46			D12163J	10			YN501-YR328
2504R	22	X2	AD	0-0	23-32-12	D45231P		12			D45279P	A05			YC051-YD170
2504R	22	X2	AD	0-0	23-34-01	D12213P		12			D12163J	9			YL951-YN260
2504R	22	X2	AD	0-0	44-21-26	D45920P		45			D12163J	9			YN501-YR328
2504Z			AD	0-0	23-32-12	D45231P				AC	D45279P			AD	YC051-YD170
2504Z			AD	0-0	23-34-01	D12213P			PERB		D12163J	PERS	1A		YL951-YN260
2504Z			AD	0-0	44-21-26	D45920P			PERB		D12163J	PERS	1A		YN501-YR328
2505B	22	X2	AE	25-11	23-32-12	D45231P		16			D45279P	B07			YC051-YD170
2505B	22	X2	AE	33-0	23-34-01	D12213P		15			D12163J	12			YL951-YN260
2505B	22	X2	AE	23-11	44-21-26	D45920P		48			D12163J	12			YN501-YR328
2505R	22	X2	AE	0-0	23-32-12	D45231P		15			D45279P	A07			YC051-YD170
2505R	22	X2	AE	0-0	23-34-01	D12213P		14			D12163J	11			YL951-YN260
2505R	22	X2	AE	0-0	44-21-26	D45920P		47			D12163J	11			YN501-YR328
2505Z			AE	0-0	23-32-12	D45231P				AE	D45279P			AF	YC051-YD170
2505Z			AE	0-0	23-34-01	D12213P			PERB		D12163J	PERS	1A		YL951-YN260
2505Z			AE	0-0	44-21-26	D45920P			PERB		D12163J	PERS	1A		YN501-YR328
2506B	22	X2	AF	25-11	23-32-12	D45231P		18			D45279P	B08			YC051-YD170
2506B	22	X2	AF	33-0	23-34-01	D12213P		17			D12163J	14			YL951-YN260
2506B	22	X2	AF	23-11	44-21-26	D45920P		52			D12163J	14			YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W5300

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5303	286A5303				VIDEO - AB0340B TO EE BAY AND TB01806 TERMINAL TRACK - AUDIO & PA (continued)										
2506R	22	X2	AF		0-0	23-32-12	D45231P	17			D45279P	A08			YC051-YD170
2506R	22	X2	AF		0-0	23-34-01	D12213P	16			D12163J	13			YL951-YN260
2506R	22	X2	AF		0-0	44-21-26	D45920P	51			D12163J	13			YN501-YR328
2506Z			AF		0-0	23-32-12	D45231P			AE	D45279P			AF	YC051-YD170
2506Z			AF		0-0	23-34-01	D12213P		PERB		D12163J	PERS	1A		YL951-YN260
2506Z			AF		0-0	44-21-26	D45920P		PERB		D12163J	PERS	1A		YN501-YR328
2507B	22	X2	AG		27-6	23-32-12	D45231P	3			D45227P	5			YC051-YD157
2507B	22	X2	AG		25-11	23-32-12	D45231P	3			D45279P	B11			YD158-YD170
2507B	22	X2	AG		27-11	23-32-12	D45231P	3			D45227P	5			YL951-YN260
2507R	22	X2	AG		0-0	23-32-12	D45231P	2			D45227P	4			YC051-YD157, YL951-YN260
2507R	22	X2	AG		0-0	23-32-12	D45231P	2			D45279P	A11			YD158-YD170
2507Z			AG		0-0	23-32-12	D45231P			AG	D45227P			AH	YC051-YD157
2507Z			AG		0-0	23-32-12	D45231P	4			D45279P	A12			YD158-YD170
2507Z			AG		0-0	23-32-12	D45231P	4			D45227P	9			YL951-YN260
2508B	22	X2	AH		27-6	23-32-12	D45231P	25			D45227P	8			YC051-YD157
2508B	22	X2	AH		25-11	23-32-12	D45231P	25			D45279P	B13			YD158-YD170
2508R	22	X2	AH		0-0	23-32-12	D45231P	24			D45227P	7			YC051-YD157
2508R	22	X2	AH		0-0	23-32-12	D45231P	24			D45279P	A13			YD158-YD170
2508Z			AH		0-0	23-32-12	D45231P			AG	D45227P			AH	YC051-YD157
2508Z			AH		0-0	23-32-12	D45231P		DED		D45279P	DED			YD158-YD170
2509B	24	OT	AI		27-6	23-32-12	D45231P	27			D45227P	11			YC051-YD157
2509B	22	X2	AI		25-11	23-32-12	D45231P	27			D45279P	B14			YD158-YD170
2509B	22	X2	AI		33-0	23-34-01	D12213P	41			D12163J	30			YL951-YN260
2509B	22	X2	AI		23-11	44-21-26	D45920P	38			D12163J	30			YN501-YR328
2509R	22	X2	AI		0-0	23-32-12	D45231P	26			D45279P	A14			YD158-YD170
2509R	22	X2	AI		0-0	23-34-01	D12213P	40			D12163J	29			YL951-YN260
2509R	22	X2	AI		0-0	44-21-26	D45920P	37			D12163J	29			YN501-YR328
2509W	24	OT	AI		0-0	23-32-12	D45231P	26			D45227P	10			YC051-YD157
2509Z			AI		0-0	23-32-12	D45231P	4			D45227P	12			YC051-YD157
2509Z			AI		0-0	23-32-12	D45231P		DED		D45279P	DED			YD158-YD170
2509Z			AI		0-0	23-34-01	D12213P		PERB		D12163J	PERS	1A		YL951-YN260
2509Z			AI		0-0	44-21-26	D45920P		PERB		D12163J	PERS	1A		YN501-YR328
2510B	24	OT	AJ		25-11	23-32-12	D45231P	32			D45279P	B10			YC051-YD157
2510B	24	OT	AJ		25-11	SPARE	D45231P	41			D45279P	A18			YD158-YD170
2510B	22	X2	AJ		27-11	23-34-01	D45231P	49			D45227P	24			YL951-YN260
2510R	22	X2	AJ		0-0	23-34-01	D45231P	48			D45227P	25			YL951-YN260
2510W	24	OT	AJ		0-0	23-32-12	D45231P	31			D45279P	A10			YC051-YD157
2510W	24	OT	AJ		0-0	SPARE	D45231P	42			D45279P	B18			YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W5300

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5303 286A5303 VIDEO - AB0340B TO EE BAY AND TB01806 TERMINAL TRACK - AUDIO & PA (continued)																
2510Z					AJ	0-0	23-32-12	D45231P	33			D45279P	B09			YC051-YD157
2510Z					AJ	0-0	SPARE	D45231P	DED			D45279P	DED			YD158-YD170
2510Z					AJ	0-0	23-34-01	D45231P	50			D45227P	26			YL951-YN260
2511B	22		X2		AK	6-4	23-34-01	D40173P	B01			D12165J	10			YL951-YN260
2511B	22		X2		AK	23-11	44-21-26	D45920P	2			D12165J	10			YN501-YR328
2511R	22		X2		AK	0-0	23-34-01	D40173P	A01			D12165J	9			YL951-YN260
2511R	22		X2		AK	0-0	44-21-26	D45920P	1			D12165J	9			YN501-YR328
2511Z					AK	0-0	23-34-01	D40173P			AE	D12165J	PERS	1A		YL951-YN260
2511Z					AK	0-0	44-21-26	D45920P			AE	D12165J	PERS	1A		YN501-YR328
2512B	22		X2		AL	6-4	23-34-01	D40173P	B02			D12165J	12			YL951-YN260
2512B	22		X2		AL	23-11	44-21-26	D45920P	4			D12165J	12			YN501-YR328
2512R	22		X2		AL	0-0	23-34-01	D40173P	A02			D12165J	11			YL951-YN260
2512R	22		X2		AL	0-0	44-21-26	D45920P	3			D12165J	11			YN501-YR328
2512Z					AL	0-0	23-34-01	D40173P			AE	D12165J	PERS	1A		YL951-YN260
2512Z					AL	0-0	44-21-26	D45920P			AE	D12165J	PERS	1A		YN501-YR328
2513B	22		X2		AM	6-4	23-34-01	D40173P	B04			D12165J	14			YL951-YN260
2513B	22		X2		AM	23-11	44-21-26	D45920P	6			D12165J	14			YN501-YR328
2513R	22		X2		AM	0-0	23-34-01	D40173P	A04			D12165J	13			YL951-YN260
2513R	22		X2		AM	0-0	44-21-26	D45920P	5			D12165J	13			YN501-YR328
2513Z					AM	0-0	23-34-01	D40173P			AE	D12165J	PERS	1A		YL951-YN260
2513Z					AM	0-0	44-21-26	D45920P			AE	D12165J	PERS	1A		YN501-YR328
2514B	22		X2		AN	6-4	23-34-01	D40173P	B05			D12165J	16			YL951-YN260
2514B	22		X2		AN	23-11	44-21-26	D45920P	8			D12165J	16			YN501-YR328
2514R	22		X2		AN	0-0	23-34-01	D40173P	A05			D12165J	15			YL951-YN260
2514R	22		X2		AN	0-0	44-21-26	D45920P	7			D12165J	15			YN501-YR328
2514Z					AN	0-0	23-34-01	D40173P			AE	D12165J	PERS	1A		YL951-YN260
2514Z					AN	0-0	44-21-26	D45920P			AE	D12165J	PERS	1A		YN501-YR328
2515B	22		X2		AP	6-4	23-34-01	D40173P	B06			D12165J	27			YL951-YN260
2515B	22		X2		AP	23-11	44-21-26	D45920P	11			D12165J	27			YN501-YR328
2515R	22		X2		AP	0-0	23-34-01	D40173P	A06			D12165J	26			YL951-YN260
2515R	22		X2		AP	0-0	44-21-26	D45920P	10			D12165J	26			YN501-YR328
2515Z					AP	0-0	23-34-01	D40173P			AG	D12165J	PERS	1A		YL951-YN260
2515Z					AP	0-0	44-21-26	D45920P			AG	D12165J	PERS	1A		YN501-YR328
2516B	22		X2		AQ	6-4	23-34-01	D40173P	B07			D12165J	29			YL951-YN260
2516B	22		X2		AQ	23-11	44-21-26	D45920P	13			D12165J	29			YN501-YR328
2516R	22		X2		AQ	0-0	23-34-01	D40173P	A07			D12165J	28			YL951-YN260
2516R	22		X2		AQ	0-0	44-21-26	D45920P	12			D12165J	28			YN501-YR328
2516Z					AQ	0-0	23-34-01	D40173P			AG	D12165J	PERS	1A		YL951-YN260
2516Z					AQ	0-0	44-21-26	D45920P			AG	D12165J	PERS	1A		YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W5300

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5303	286A5303			VIDEO - AB0340B TO EE BAY AND TB01806 TERMINAL TRACK - AUDIO & PA (continued)											
2517B	22	X2	AR		6-4	23-34-01	D40173P	B09			D12165J	31			YL951-YN260
2517B	22	X2	AR		23-11	44-21-26	D45920P	15			D12165J	31			YN501-YR328
2517R	22	X2	AR		0-0	23-34-01	D40173P	A09			D12165J	30			YL951-YN260
2517R	22	X2	AR		0-0	44-21-26	D45920P	14			D12165J	30			YN501-YR328
2517Z			AR		0-0	23-34-01	D40173P			AG	D12165J	PERS	1A		YL951-YN260
2517Z			AR		0-0	44-21-26	D45920P			AG	D12165J	PERS	1A		YN501-YR328
2518B	24	0T	AS		33-0	23-34-01	D12213P	54			D12163J	27			YL951-YN260
2518B	22	X2	AS		23-11	44-21-26	D45920P	54			D12163J	27			YN501-YR328
2518R	22	X2	AS		0-0	44-21-26	D45920P	53			D12163J	26			YN501-YR328
2518W	24	0T	AS		0-0	23-34-01	D12213P	53			D12163J	26			YL951-YN260
2518Z			AS		0-0	23-34-01	D12213P	PERB			D12163J	PERS	1A		YL951-YN260
2518Z			AS		0-0	44-21-26	D45920P	PERB			D12163J	PERS	1A		YN501-YR328
2519B	22	X2	AT		6-3	23-34-01	D40173P	B11			D12167J	10			YL951-YN260
2519B	22	X2	AT		23-10	44-21-26	D45920P	20			D12167J	10			YN501-YR328
2519R	22	X2	AT		0-0	23-34-01	D40173P	A11			D12167J	9			YL951-YN260
2519R	22	X2	AT		0-0	44-21-26	D45920P	19			D12167J	9			YN501-YR328
2519Z			AT		0-0	23-34-01	D40173P			AI	D12167J	PERS	1A		YL951-YN260
2519Z			AT		0-0	44-21-26	D45920P			AI	D12167J	PERS	1A		YN501-YR328
2520B	22	X2	AU		6-3	23-34-01	D40173P	B12			D12167J	12			YL951-YN260
2520B	22	X2	AU		23-10	44-21-26	D45920P	22			D12167J	12			YN501-YR328
2520R	22	X2	AU		0-0	23-34-01	D40173P	A12			D12167J	11			YL951-YN260
2520R	22	X2	AU		0-0	44-21-26	D45920P	21			D12167J	11			YN501-YR328
2520Z			AU		0-0	23-34-01	D40173P			AI	D12167J	PERS	1A		YL951-YN260
2520Z			AU		0-0	44-21-26	D45920P			AI	D12167J	PERS	1A		YN501-YR328
2521B	22	X2	AV		6-3	23-34-01	D40173P	B14			D12167J	14			YL951-YN260
2521B	22	X2	AV		23-10	44-21-26	D45920P	24			D12167J	14			YN501-YR328
2521R	22	X2	AV		0-0	23-34-01	D40173P	A14			D12167J	13			YL951-YN260
2521R	22	X2	AV		0-0	44-21-26	D45920P	23			D12167J	13			YN501-YR328
2521Z			AV		0-0	23-34-01	D40173P			AI	D12167J	PERS	1A		YL951-YN260
2521Z			AV		0-0	44-21-26	D45920P			AI	D12167J	PERS	1A		YN501-YR328
2522B	22	X2	AW		6-3	23-34-01	D40173P	B15			D12167J	16			YL951-YN260
2522B	22	X2	AW		23-10	44-21-26	D45920P	26			D12167J	16			YN501-YR328
2522R	22	X2	AW		0-0	23-34-01	D40173P	A15			D12167J	15			YL951-YN260
2522R	22	X2	AW		0-0	44-21-26	D45920P	25			D12167J	15			YN501-YR328
2522Z			AW		0-0	23-34-01	D40173P			AI	D12167J	PERS	1A		YL951-YN260
2522Z			AW		0-0	44-21-26	D45920P			AI	D12167J	PERS	1A		YN501-YR328
2523B	22	X2	AX		6-3	23-34-01	D40173P	B16			D12167J	27			YL951-YN260
2523B	22	X2	AX		23-10	44-21-26	D45920P	29			D12167J	27			YN501-YR328
2523R	22	X2	AX		0-0	23-34-01	D40173P	A16			D12167J	26			YL951-YN260

WIRE LIST

D280A108

91-21-11

Section W5300

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5303 286A5303 VIDEO - AB0340B TO EE BAY AND TB01806 TERMINAL TRACK - AUDIO & PA (continued)																
2523R		22		X2	AX	0-0	44-21-26	D45920P	28			D12167J	26			YN501-YR328
2523Z					AX	0-0	23-34-01	D40173P			AK	D12167J	PERS	1A		YL951-YN260
2523Z					AX	0-0	44-21-26	D45920P			AK	D12167J	PERS	1A		YN501-YR328
2524B		22		X2	AY	6-3	23-34-01	D40173P	B17			D12167J	29			YL951-YN260
2524B		22		X2	AY	23-10	44-21-26	D45920P	31			D12167J	29			YN501-YR328
2524R		22		X2	AY	0-0	23-34-01	D40173P	A17			D12167J	28			YL951-YN260
2524R		22		X2	AY	0-0	44-21-26	D45920P	30			D12167J	28			YN501-YR328
2524Z					AY	0-0	23-34-01	D40173P			AK	D12167J	PERS	1A		YL951-YN260
2524Z					AY	0-0	44-21-26	D45920P			AK	D12167J	PERS	1A		YN501-YR328
2525B		22		X2	AZ	6-3	23-34-01	D40173P	B19			D12167J	31			YL951-YN260
2525B		22		X2	AZ	23-10	44-21-26	D45920P	33			D12167J	31			YN501-YR328
2525R		22		X2	AZ	0-0	23-34-01	D40173P	A19			D12167J	30			YL951-YN260
2525R		22		X2	AZ	0-0	44-21-26	D45920P	32			D12167J	30			YN501-YR328
2525Z					AZ	0-0	23-34-01	D40173P			AK	D12167J	PERS	1A		YL951-YN260
2525Z					AZ	0-0	44-21-26	D45920P			AK	D12167J	PERS	1A		YN501-YR328
2526B		22		X2	BA	6-3	23-34-01	D40173P	B20			D12167J	33			YL951-YN260
2526B		22		X2	BA	23-10	44-21-26	D45920P	35			D12167J	33			YN501-YR328
2526R		22		X2	BA	0-0	23-34-01	D40173P	A20			D12167J	32			YL951-YN260
2526R		22		X2	BA	0-0	44-21-26	D45920P	34			D12167J	32			YN501-YR328
2526Z					BA	0-0	23-34-01	D40173P			AK	D12167J	PERS	1A		YL951-YN260
2526Z					BA	0-0	44-21-26	D45920P			AK	D12167J	PERS	1A		YN501-YR328
2527B		22		X2	BB	6-4	23-34-01	D40173P	B10			D12165J	33			YL951-YN260
2527B		22		X2	BB	23-11	44-21-26	D45920P	17			D12165J	33			YN501-YR328
2527R		22		X2	BB	0-0	23-34-01	D40173P	A10			D12165J	32			YL951-YN260
2527R		22		X2	BB	0-0	44-21-26	D45920P	16			D12165J	32			YN501-YR328
2527Z					BB	0-0	23-34-01	D40173P			AG	D12165J	PERS	1A		YL951-YN260
2527Z					BB	0-0	44-21-26	D45920P			AG	D12165J	PERS	1A		YN501-YR328
3001B		22		PC	CA	25-11	23-32-12	D45231P	32			D45279P	B10			YD158-YD170
3001B		22		PC	GA	33-0	23-34-01	D12213P	32			D12163J	19			YL951-YN260
3001R		22		PC	CA	0-0	23-32-12	D45231P	31			D45279P	A10			YD158-YD170
3001R		22		PC	GA	0-0	23-34-01	D12213P	31			D12163J	18			YL951-YN260
3001Y		22		PC	CA	0-0	23-32-12	D45231P	33			D45279P	B09			YD158-YD170
3001Y		22		PC	GA	0-0	23-34-01	D12213P	33			D12163J	20			YL951-YN260
FRAA						0-0	23-32-12	D45231P			AA	D45231P	9			YC051-YD170
FRAB						0-0	23-32-12	D45279P			AB	D45279P	A03			YC051-YD170
FRAC						0-0	23-32-12	D45231P			AC	D45231P	14			YC051-YD170
FRAD						0-0	23-32-12	D45279P			AD	D45279P	A06			YC051-YD170
FRAE						0-0	23-32-12	D45231P			AE	D45231P	19			YC051-YD170
FRAE						0-0	23-34-01	D40173P			AE	D40173P	A08			YL951-YN260

WIRE LIST

D280A108

91-21-11

Section W5300

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5303 286A5303 VIDEO - AB0340B TO EE BAY AND TB01806 TERMINAL TRACK - AUDIO & PA (continued)																
	FRAE					0-0	44-21-26	D45920P				AE	D45920P		9	YN501-YR328
	FRAF					0-0	23-32-12	D45279P				AF	D45279P		A09	YC051-YD170
	FRAG					0-0	23-32-12	D45231P				AG	D45231P		39	YC051-YD157
	FRAG					0-0	23-34-01	D40173P				AG	D40173P		B08	YL951-YN260
	FRAG					0-0	44-21-26	D45920P				AG	D45920P		18	YN501-YR328
	FRAH					0-0	23-32-12	D45227P				AH	D45227P		13	YC051-YD157
	FRAI					0-0	23-34-01	D40173P				AI	D40173P		A18	YL951-YN260
	FRAI					0-0	44-21-26	D45920P				AI	D45920P		27	YN501-YR328
	FRAK					0-0	23-34-01	D40173P				AK	D40173P		B18	YL951-YN260
	FRAK					0-0	44-21-26	D45920P				AK	D45920P		36	YN501-YR328
	YAAA					0-0	23-34-01	D12163J		PERB			D12213P		PERB	YL951-YN260
	YAAA					0-0	44-21-26	D12163J		PERB			OAS0001			YN501-YR328
	YAAB					0-0	23-34-01	D12165J		PERB			OAS0001			YL951-YN260
	YAAB					0-0	44-21-26	D12165J		PERB			OAS0001			YN501-YR328
	YAAC					0-0	23-34-01	D12167J		PERB			OAS0001			YL951-YN260
	YAAC					0-0	44-21-26	D12167J		PERB			OAS0001			YN501-YR328
	YAAD					0-0	23-34-01	OAS0001					D40173P		S/R	YL951-YN260
	YAAD					0-0	44-21-26	OAS0001					D45920P		PERB	YN501-YR328

WIRE LIST

D280A108

91-21-11
Section W5300
Page 9 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	
W5310	286A5310				E2 TO E3									
0502	22		PA		7-3	SPARE	D40446P	A03			D40450P	A14		YC051-YC055
0502	22		PA		7-6	SPARE	D40446P	A03			D40450P	A14		YC056-YL954, YN231-YN235
2601B	24	Y2	SA		7-7	73-24-11	D40448P	A05			D40450P	A07		YC051-YC055
2601B	24	Y2	SA		7-11	73-24-11	D40448P	A05			D40450P	A07		YC056-YR328
2601R	24	Y2	SA		0-0	73-24-11	D40448P	B05			D40450P	B07		ALL
2601Z			SA		0-0	73-24-11	D40448P	PERG	1F		D40450P	PERG	1F	ALL
2602B	24	Y2	SB		7-7	73-24-12	D40448P	A02			D40450P	A02		YC051-YC055
2602B	24	Y2	SB		7-11	73-24-12	D40448P	A02			D40450P	A02		YC056-YR328
2602R	24	Y2	SB		0-0	73-24-12	D40448P	B02			D40450P	B02		ALL
2602Z			SB		0-0	73-24-12	D40448P	PERG	1F		D40450P	PERG	1F	ALL
2603B	22	VX	SC		7-2	77-31-11	D40726P	A01			D40450P	A08		YC051-YC055
2603B	22	VX	SC		7-6	77-31-11	D40726P	A01			D40450P	A08		YC056-YL954, YN231-YN235
2603B	22	VX	SC		7-6	77-31-11	D40446P	A01			D40450P	A08		YL955-YL999, YN236-YR328
2603W	22	VX	SC		0-0	77-31-11	D40726P	B01			D40450P	B08		YC051-YL954, YN231-YN235
2603W	22	VX	SC		0-0	77-31-11	D40446P	B01			D40450P	B08		YL955-YL999, YN236-YR328
2603Z			SC		0-0	77-31-11	D40726P	A02			D40450P	A09		YC051-YL954, YN231-YN235
2603Z			SC		0-0	77-31-11	D40446P	A02			D40450P	A09		YL955-YL999, YN236-YR328
2605B	22	PB	SE		7-3	78-36-11	D40446P	A05			D40450P	A03		YC051-YC055
2605B	22	PB	SE		7-6	78-36-11	D40446P	A05			D40450P	A03		YC056-YR328
2605R	22	PB	SE		0-0	78-36-11	D40446P	B05			D40450P	B03		ALL
2606B	22	PB	SF		7-3	78-36-11	D40446P	A06			D40450P	A04		YC051-YC055
2606B	22	PB	SF		7-6	78-36-11	D40446P	A06			D40450P	A04		YC056-YR328
2606R	22	PB	SF		0-0	78-36-11	D40446P	B06			D40450P	B04		ALL
2607B	24	Y2	SG		7-7	77-12-21	D40448P	A06			D40450P	A11		YC051-YC055
2607B	24	Y2	SG		7-11	77-12-21	D40448P	A06			D40450P	A11		YC056-YR328
2607R	24	Y2	SG		0-0	77-12-21	D40448P	B06			D40450P	B11		ALL
2607Z			SG		0-0	77-12-21	D40448P	PERG	1F		D40450P	PERG	1F	ALL
2608B	24	Y2	SH		2-3	77-31-11	D40726P	A04			D40448P	A03		YC051-YC055
2608B	24	Y2	SH		2-2	77-31-11	D40726P	A04			D40448P	A03		YC056-YL954, YN231-YN235
2608B	24	Y2	SH		2-3	77-31-11	D40446P	A04			D40448P	A03		YL955-YL999, YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W5310

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5310	286A5310				E2 TO E3 (continued)										
2608R	24	Y2	SH		0-0	77-31-11	D40726P	B04			D40448P	B03			YC051-YL954, YN231-YN235
2608R	24	Y2	SH		0-0	77-31-11	D40446P	B04			D40448P	B03			YL955-YL999, YN236-YR328
2608Z			SH		0-0	77-31-11	D40726P	PERG	1F		D40448P	PERG	1F		YC051-YL954, YN231-YN235
2608Z			SH		0-0	77-31-11	D40446P	PERG	1F		D40448P	PERG	1F		YL955-YL999, YN236-YR328
2609B	24	Y2	SI		2-3	77-31-11	D40726P	A05			D40448P	A07			YC051-YC055
2609B	24	Y2	SI		2-2	77-31-11	D40726P	A05			D40448P	A07			YC056-YL954, YN231-YN235
2609B	24	Y2	SI		2-3	77-31-11	D40446P	A07			D40448P	A07			YL955-YL999, YN236-YR328
2609R	24	Y2	SI		0-0	77-31-11	D40726P	B05			D40448P	B07			YC051-YL954, YN231-YN235
2609R	24	Y2	SI		0-0	77-31-11	D40446P	B07			D40448P	B07			YL955-YL999, YN236-YR328
2609Z			SI		0-0	77-31-11	D40726P	PERG	1F		D40448P	PERG	1F		YC051-YL954, YN231-YN235
2609Z			SI		0-0	77-31-11	D40446P	PERG	1F		D40448P	PERG	1F		YL955-YL999, YN236-YR328
2610B	24	Y2	SJ		2-3	77-31-11	D40726P	A06			D40448P	A08			YC051-YC055
2610B	24	Y2	SJ		2-2	77-31-11	D40726P	A06			D40448P	A08			YC056-YL954, YN231-YN235
2610B	24	Y2	SJ		2-3	77-31-11	D40446P	A03			D40448P	A08			YL955-YL999, YN236-YR328
2610R	24	Y2	SJ		0-0	77-31-11	D40726P	B06			D40448P	B08			YC051-YL954, YN231-YN235
2610R	24	Y2	SJ		0-0	77-31-11	D40446P	B03			D40448P	B08			YL955-YL999, YN236-YR328
2610Z			SJ		0-0	77-31-11	D40726P	PERG	1F		D40448P	PERG	1F		YC051-YL954, YN231-YN235
2610Z			SJ		0-0	77-31-11	D40446P	PERG	1F		D40448P	PERG	1F		YL955-YL999, YN236-YR328
2611B	24	Y2	SD		8-10	31-35-04	D40350P	B04			D40348P	B11			YL963-YL999, YN236-YR328
2611R	24	Y2	SD		0-0	31-35-04	D40350P	B03			D40348P	A11			YL963-YL999, YN236-YR328

WIRE LIST
D280A108

91-21-11
Section W5310
Page 2
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5310	286A5310			E2 TO E3 (continued)											
2611Z				SD	0-0	31-35-04	D40350P	PERG	1F		D40348P	PERG	1F		YL963-YL999, YN236-YR328
2612B	20	X2	B8		8-11	31-35-05	D40940P	B05			D40348P	B06			YL963-YL999, YN236-YR328
2612R	20	X2	B8		0-0	31-35-05	D40940P	A05			D40348P	A06			YL963-YL999, YN236-YR328
2612Z				B8	0-0	31-35-05	D40940P	PERG	1F		D40348P	PERG	1F		YL963-YL999, YN236-YR328
2802B	24	Y2	B8		7-3	SPARE	D40446P	A02			D40450P	A13			YC051-YC055
2802B	24	Y2	B8		7-6	SPARE	D40446P	A02			D40450P	A13			YC056-YL954, YN231-YN235
2802R	24	Y2	B8		0-0	SPARE	D40446P	B02			D40450P	B13			YC051-YL954, YN231-YN235
2802Z				B8	0-0	SPARE	D40446P	PERG	1F		D40450P	PERG	1F		YC051-YL954, YN231-YN235
5501	24	PK			7-3	21-31-24	D40446P	A10			D40450P	A06			YC051-YC055
5501	24	PK			7-6	21-31-24	D40446P	A10			D40450P	A06			YC056-YR328
5502	24	PK			7-3	SPARE	D40446P	B10			D40450P	B06			YC051-YC055
5502	24	PK			7-6	SPARE	D40446P	B10			D40450P	B06			YC056-YR328
6001	24	B6			7-7	80-11-11	D40450P	A01			D40448P	A01			YC051-YC055
6001	24	B6			7-11	80-11-11	D40450P	A01			D40448P	A01			YC056-YR328
6002	24	B6			7-7	80-11-11	D40450P	B01			D40448P	B01			YC051-YC055
6002	24	B6			7-11	80-11-11	D40450P	B01			D40448P	B01			YC056-YR328
6003	24	PK			2-3	SPARE	D40446P	B03			D40448P	B09			YC051-YL954, YN231-YN235
6004	22	PA			7-11	30-31-12	D40448P	B04			D40450P	B05			YL968-YL999, YN236-YR328
6005	22	PA			7-11	30-31-12	D40448P	A04			D40450P	A05			YL968-YL999, YN236-YR328
6053	24	PK			8-11	31-35-05	D40940P	A08			D40348P	A05			YL963-YL999, YN236-YR328
6054	24	PK			8-11	31-35-05	D40940P	B02			D40348P	B05			YL963-YL999, YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W5310

Page 3 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To				
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5331	286A5331			CMU INTERFACES E3-3 (LEFT)											
0001	22		PA		9-8	23-27-31	D04115P		B17		D43345P		B17		YD158-YR328
0002	22		PA		9-10	23-27-38	D04117P		A01		D43347P		A01		YD158-YR328
0003	22		PA		9-10	23-27-38	D04117P		B01		D43347P		B01		YD158-YR328
0004	22		PA		9-10	23-27-38	D04117P		A02		D43347P		A02		YD158-YR328
0005	22		PA		9-10	23-27-38	D04117P		B02		D43347P		B02		YD158-YR328
0006	22		PA		9-10	23-27-38	D04117P		A03		D43347P		A03		YD158-YR328
0007	22		PA		9-10	23-27-38	D04117P		B03		D43347P		B03		YD158-YR328
0008	24		PK		9-8	23-27-39	D04115P		A17		D43345P		A17		YD158-YR328
0022	24		PK		9-10	SPARE	D43347P		A05		D04117P		A05		YD158-YR328
0023	24		PK		9-10	SPARE	D43347P		B05		D04117P		B05		YD158-YR328
0024	24		PK		9-10	SPARE	D43347P		A06		D04117P		A06		YD158-YR328
0025	24		PK		9-10	SPARE	D43347P		B06		D04117P		B06		YD158-YR328
0030	22		PA		9-8	23-27-31	D04115P		A20		D43345P		A20		YL951-YL954
0030	22		PA		9-8	SPARE	D04115P		A20		D43345P		A20		YL955-YL999, YN236-YN260
0030	22		PA		9-8	MULTI	D04115P		A20		D43345P		A20		YN231-YN235
0031	22		PA		9-8	23-27-31	D04115P		B20		D43345P		B20		YL951-YL954
0031	22		PA		9-8	SPARE	D04115P		B20		D43345P		B20		YL955-YL999, YN236-YN260
0031	22		PA		9-8	MULTI	D04115P		B20		D43345P		B20		YN231-YN235
2501B	24		Y2	AA	9-8	23-27-32	D04115P		B07		D43345P		B07		YD158-YN260
2501B	24		Y2	AA	9-8	SPARE	D04115P		B07		D43345P		B07		YN501-YR328
2501R	24		Y2	AA	0-0	23-27-32	D04115P		A07		D43345P		A07		YD158-YN260
2501R	24		Y2	AA	0-0	SPARE	D04115P		A07		D43345P		A07		YN501-YR328
2501Z				AA	0-0	23-27-32	D04115P	PERG	1F		D43345P	PERG	1F		YD158-YN260
2501Z				AA	0-0	SPARE	D04115P	PERG	1F		D43345P	PERG	1F		YN501-YR328
2502B	24		Y2	AB	9-8	23-27-32	D04115P		B08		D43345P		B08		YD158-YR328
2502R	24		Y2	AB	0-0	23-27-32	D04115P		A08		D43345P		A08		YD158-YR328
2502Z				AB	0-0	23-27-32	D04115P	PERG	1F		D43345P	PERG	1F		YD158-YR328
2503B	24		Y2	AC	9-8	SPARE	D04115P		B09		D43345P		B09		YD158-YN260
2503B	24		Y2	AC	9-8	23-27-34	D04115P		B09		D43345P		B09		YN501-YR328
2503R	24		Y2	AC	0-0	SPARE	D04115P		A09		D43345P		A09		YD158-YN260
2503R	24		Y2	AC	0-0	23-27-34	D04115P		A09		D43345P		A09		YN501-YR328
2503Z				AC	0-0	SPARE	D04115P	PERG	1F		D43345P	PERG	1F		YD158-YN260
2503Z				AC	0-0	23-27-34	D04115P	PERG	1F		D43345P	PERG	1F		YN501-YR328
2504B	24		Y2	AD	9-8	SPARE	D04115P		B10		D43345P		B10		YD158-YR328
2504R	24		Y2	AD	0-0	SPARE	D04115P		A10		D43345P		A10		YD158-YR328
2504Z				AD	0-0	SPARE	D04115P	PERG	1F		D43345P	PERG	1F		YD158-YR328
2505B	24		Y2	AE	9-8	SPARE	D04115P		B06		D43345P		B06		YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W5330

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5331		286A5331				CMU INTERFACES E3-3 (LEFT) (continued)										
2505R		24	Y2	AE		0-0	SPARE	D04115P	A06			D43345P	A06			YD158-YR328
2505Z				AE		0-0	SPARE	D04115P	PERG	1F		D43345P	PERG	1F		YD158-YR328
2506B		24	Y2	AF		9-8	SPARE	D04115P	B05			D43345P	B05			YD158-YD170, YN501-YR328
2506R		24	Y2	AF		0-0	SPARE	D04115P	A05			D43345P	A05			YD158-YD170, YN501-YR328
2506Z				AF		0-0	SPARE	D04115P	PERG	1F		D43345P	PERG	1F		YD158-YD170, YN501-YR328
2507B		24	Y2	AG		9-8	23-27-34	D04115P	B04			D43345P	B04			YD158-YD170
2507B		24	Y2	AG		9-8	SPARE	D04115P	B04			D43345P	B04			YN501-YR328
2507R		24	Y2	AG		0-0	23-27-34	D04115P	A04			D43345P	A04			YD158-YD170
2507R		24	Y2	AG		0-0	SPARE	D04115P	A04			D43345P	A04			YN501-YR328
2507Z				AG		0-0	23-27-34	D04115P	PERG	1F		D43345P	PERG	1F		YD158-YD170
2507Z				AG		0-0	SPARE	D04115P	PERG	1F		D43345P	PERG	1F		YN501-YR328
2508B		24	Y2	AH		9-8	SPARE	D04115P	B11			D43345P	B11			YD158-YR328
2508R		24	Y2	AH		0-0	SPARE	D04115P	A11			D43345P	A11			YD158-YR328
2508Z				AH		0-0	SPARE	D04115P	PERG	1F		D43345P	PERG	1F		YD158-YR328
2509B		24	Y2	AI		9-8	23-27-37	D04115P	B12			D43345P	B12			YD158-YR328
2509R		24	Y2	AI		0-0	23-27-37	D04115P	A12			D43345P	A12			YD158-YR328
2509Z				AI		0-0	23-27-37	D04115P	PERG	1F		D43345P	PERG	1F		YD158-YR328
2510B		24	Y2	AJ		9-8	23-27-37	D04115P	B13			D43345P	B13			YD158-YR328
2510R		24	Y2	AJ		0-0	23-27-37	D04115P	A13			D43345P	A13			YD158-YR328
2510Z				AJ		0-0	23-27-37	D04115P	PERG	1F		D43345P	PERG	1F		YD158-YR328
2511B		24	Y2	AK		9-8	SPARE	D04115P	B14			D43345P	B14			YD158-YR328
2511R		24	Y2	AK		0-0	SPARE	D04115P	A14			D43345P	A14			YD158-YR328
2511Z				AK		0-0	SPARE	D04115P	PERG	1F		D43345P	PERG	1F		YD158-YR328
2512B		24	Y2	AL		9-10	23-27-38	D04117P	B11			D43347P	B11			YD158-YR328
2512R		24	Y2	AL		0-0	23-27-38	D04117P	A11			D43347P	A11			YD158-YR328
2512Z				AL		0-0	23-27-38	D04117P	PERG	1F		D43347P	PERG	1F		YD158-YR328
2513B		24	Y2	AM		9-8	23-27-39	D04115P	B15			D43345P	B15			YD158-YR328
2513R		24	Y2	AM		0-0	23-27-39	D04115P	A15			D43345P	A15			YD158-YR328
2513Z				AM		0-0	23-27-39	D04115P	PERG	1F		D43345P	PERG	1F		YD158-YR328
2514B		24	Y2	AN		9-10	MULTI	D04117P	B08			D43347P	B08			YD158-YD170
2514B		24	Y2	AN		9-10	31-35-02	D04117P	B08			D43347P	B08			YL951-YR328
2514R		24	Y2	AN		0-0	MULTI	D04117P	A08			D43347P	A08			YD158-YD170
2514R		24	Y2	AN		0-0	31-35-02	D04117P	A08			D43347P	A08			YL951-YR328
2514Z				AN		0-0	MULTI	D04117P	PERG	1F		D43347P	PERG	1F		YD158-YD170
2514Z				AN		0-0	31-35-02	D04117P	PERG	1F		D43347P	PERG	1F		YL951-YR328
2515B		24	Y2	AO		9-10	MULTI	D04117P	B07			D43347P	B07			YD158-YD170

WIRE LIST

D280A108

91-21-11

Section W5330

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5331	286A5331				CMU INTERFACES E3-3 (LEFT) (continued)											
2515B	24	Y2	AO		9-10	31-35-02		D04117P	B07			D43347P	B07			YL951-YR328
2515R	24	Y2	AO		0-0	MULTI		D04117P	A07			D43347P	A07			YD158-YD170
2515R	24	Y2	AO		0-0	31-35-02		D04117P	A07			D43347P	A07			YL951-YR328
2515Z			AO		0-0	MULTI		D04117P	PERG	1F		D43347P	PERG	1F		YD158-YD170
2515Z			AO		0-0	31-35-02		D04117P	PERG	1F		D43347P	PERG	1F		YL951-YR328
2516B	24	Y2	AP		9-10	MULTI		D04117P	B10			D43347P	B10			YD158-YD170
2516B	24	Y2	AP		9-10	31-62-15		D04117P	B10			D43347P	B10			YL951-YN260
2516B	24	Y2	AP		9-10	SPARE		D04117P	B10			D43347P	B10			YN501-YR328
2516R	24	Y2	AP		0-0	MULTI		D04117P	A10			D43347P	A10			YD158-YD170
2516R	24	Y2	AP		0-0	31-62-15		D04117P	A10			D43347P	A10			YL951-YN260
2516R	24	Y2	AP		0-0	SPARE		D04117P	A10			D43347P	A10			YN501-YR328
2516Z			AP		0-0	MULTI		D04117P	PERG	1F		D43347P	PERG	1F		YD158-YD170
2516Z			AP		0-0	31-62-15		D04117P	PERG	1F		D43347P	PERG	1F		YL951-YN260
2516Z			AP		0-0	SPARE		D04117P	PERG	1F		D43347P	PERG	1F		YN501-YR328
2517B	24	Y2	BA		9-10	31-32-15		D04117P	B12			D43347P	B12			YD158-YR328
2517R	24	Y2	BA		0-0	31-32-15		D04117P	A12			D43347P	A12			YD158-YR328
2517Z			BA		0-0	31-32-15		D04117P	PERG	1F		D43347P	PERG	1F		YD158-YR328
2518B	24	Y2	AR		9-10	31-33-01		D04117P	B09			D43347P	B09			YD158-YR328
2518R	24	Y2	AR		0-0	31-33-01		D04117P	A09			D43347P	A09			YD158-YR328
2518Z			AR		0-0	31-33-01		D04117P	PERG	1F		D43347P	PERG	1F		YD158-YR328
2519B	24	Y2	AS		9-10	34-61-23		D04117P	B13			D43347P	B13			YD158-YR328
2519R	24	Y2	AS		0-0	34-61-23		D04117P	A13			D43347P	A13			YD158-YR328
2519Z			AS		0-0	34-61-23		D04117P	PERG	1F		D43347P	PERG	1F		YD158-YR328
2520B	24	Y2	AT		9-10	34-61-25		D04117P	B14			D43347P	B14			YD158-YN260
2520B	24	Y2	AT		9-10	SPARE		D04117P	B14			D43347P	B14			YN501-YR328
2520R	24	Y2	AT		0-0	34-61-25		D04117P	A14			D43347P	A14			YD158-YN260
2520R	24	Y2	AT		0-0	SPARE		D04117P	A14			D43347P	A14			YN501-YR328
2520Z			AT		0-0	34-61-25		D04117P	PERG	1F		D43347P	PERG	1F		YD158-YN260
2520Z			AT		0-0	SPARE		D04117P	PERG	1F		D43347P	PERG	1F		YN501-YR328
2521B	24	Y2	AU		9-10	34-61-25		D04117P	B15			D43347P	B15			YD158-YN260
2521B	24	Y2	AU		9-10	SPARE		D04117P	B15			D43347P	B15			YN501-YR328
2521R	24	Y2	AU		0-0	34-61-25		D04117P	A15			D43347P	A15			YD158-YN260
2521R	24	Y2	AU		0-0	SPARE		D04117P	A15			D43347P	A15			YN501-YR328
2521Z			AU		0-0	34-61-25		D04117P	PERG	1F		D43347P	PERG	1F		YD158-YN260
2521Z			AU		0-0	SPARE		D04117P	PERG	1F		D43347P	PERG	1F		YN501-YR328
2522B	24	Y2	AV		9-10	34-61-25		D04117P	B16			D43347P	B16			YD158-YN260
2522B	24	Y2	AV		9-10	SPARE		D04117P	B16			D43347P	B16			YN501-YR328
2522R	24	Y2	AV		0-0	34-61-25		D04117P	A16			D43347P	A16			YD158-YN260
2522R	24	Y2	AV		0-0	SPARE		D04117P	A16			D43347P	A16			YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W5330

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type
W5331	286A5331				CMU INTERFACES E3-3 (LEFT) (continued)										
2522Z				AV	0-0	34-61-25	D04117P	PERG	1F		D43347P	PERG	1F		YD158-YN260
2522Z				AV	0-0	SPARE	D04117P	PERG	1F		D43347P	PERG	1F		YN501-YR328
2523B	24	Y2		AW	9-10	34-61-21	D04117P		B17		D43347P		B17		YD158-YR328
2523R	24	Y2		AW	0-0	34-61-21	D04117P		A17		D43347P		A17		YD158-YR328
2523Z				AW	0-0	34-61-21	D04117P	PERG	1F		D43347P	PERG	1F		YD158-YR328
2524B	24	Y2		AX	9-8	SPARE	D04115P		B16		D43345P		B16		YD158-YR328
2524R	24	Y2		AX	0-0	SPARE	D04115P		A16		D43345P		A16		YD158-YR328
2524Z				AX	0-0	SPARE	D04115P	PERG	1F		D43345P	PERG	1F		YD158-YR328
2526B	24	Y2		AZ	9-10	34-45-21	D04117P		B18		D43347P		B18		YD158-YR328
2526R	24	Y2		AZ	0-0	34-45-21	D04117P		A18		D43347P		A18		YD158-YR328
2526Z				AZ	0-0	34-45-21	D04117P	PERG	1F		D43347P	PERG	1F		YD158-YR328
2527B	24	Y2		AQ	9-8	SPARE	D04115P		B01		D43345P		B01		YD158-YN260
2527B	24	Y2		AQ	9-8	23-27-34	D04115P		B01		D43345P		B01		YN501-YR328
2527R	24	Y2		AQ	0-0	SPARE	D04115P		A01		D43345P		A01		YD158-YN260
2527R	24	Y2		AQ	0-0	23-27-34	D04115P		A01		D43345P		A01		YN501-YR328
2527Z				AQ	0-0	SPARE	D04115P	PERG	1F		D43345P	PERG	1F		YD158-YN260
2527Z				AQ	0-0	23-27-34	D04115P	PERG	1F		D43345P	PERG	1F		YN501-YR328
2528B	24	Y2		BB	9-8	23-32-21	D04115P		B02		D43345P		B02		YD158-YD170, YN501-YR328
2528B	22	X2		BB	9-8	SPARE	D04115P		B02		D43345P		B02		YL951-YN260
2528R	24	Y2		BB	0-0	23-32-21	D04115P		A02		D43345P		A02		YD158-YD170, YN501-YR328
2528R	22	X2		BB	0-0	SPARE	D04115P		A02		D43345P		A02		YL951-YN260
2528Z				BB	0-0	23-32-21	D04115P	PERG	1F		D43345P	PERG	1F		YD158-YD170, YN501-YR328
2528Z				BB	0-0	SPARE	D04115P	PERG	1F		D43345P	PERG	1F		YL951-YN260
2529B	24	Y2		BC	9-8	23-27-36	D04115P		B18		D43345P		B18		YD158-YD170, YN501-YR328
2529B	24	Y2		BC	9-8	SPARE	D04115P		B18		D43345P		B18		YL951-YN260
2529R	24	Y2		BC	0-0	23-27-36	D04115P		A18		D43345P		A18		YD158-YD170, YN501-YR328
2529R	24	Y2		BC	0-0	SPARE	D04115P		A18		D43345P		A18		YL951-YN260
2529Z				BC	0-0	23-27-36	D04115P	PERG	1F		D43345P	PERG	1F		YD158-YD170, YN501-YR328
2529Z				BC	0-0	SPARE	D04115P	PERG	1F		D43345P	PERG	1F		YL951-YN260
2530B	24	Y2		BD	9-8	23-27-36	D04115P		B19		D43345P		B19		YD158-YD170, YN501-YR328
2530B	24	Y2		BD	9-8	SPARE	D04115P		B19		D43345P		B19		YL951-YN260

WIRE LIST

D280A108

91-21-11

Section W5330

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5331	286A5331			CMU INTERFACES E3-3 (LEFT) (continued)											
2530R	24	Y2	BD		0-0	23-27-36	D04115P	A19			D43345P	A19			YD158-YD170, YN501-YR328
2530R	24	Y2	BD		0-0	SPARE	D04115P	A19			D43345P	A19			YL951-YN260
2530Z			BD		0-0	23-27-36	D04115P	PERG	1F		D43345P	PERG	1F		YD158-YD170, YN501-YR328
2530Z			BD		0-0	SPARE	D04115P	PERG	1F		D43345P	PERG	1F		YL951-YN260
2532B	24	Y2	BF		9-8	SPARE	D04115P	B03			D43345P	B03			YD158-YD170, YN501-YR328
2532B	24	Y2	BF		9-8	23-27-33	D04115P	B03			D43345P	B03			YL951-YN260
2532R	24	Y2	BF		0-0	23-27-33	D04115P	A03			D43345P	A03			YD158-YN260
2532R	24	Y2	BF		0-0	SPARE	D04115P	A03			D43345P	A03			YN501-YR328
2532Z			BF		0-0	23-27-33	D04115P	PERG	1F		D43345P	PERG	1F		YD158-YN260
2532Z			BF		0-0	SPARE	D04115P	PERG	1F		D43345P	PERG	1F		YN501-YR328
2561B	24	M5	CA		9-10	SPARE	D43347P	B20			D04117P	B20			YD158-YR328
2561R	24	M5	CA		0-0	SPARE	D43347P	A20			D04117P	A20			YD158-YR328
2561ZI			CA		0-0	SPARE	D43347P	A19			D04117P	A19			YD158-YR328
2561ZO			CA		0-0	SPARE	D43347P	PERG	1F		D04117P	PERG	1F		YD158-YR328
2563B	24	Y2	AY		9-8	23-27-39	D04115P	B04			D43345P	B04			YL951-YL954
2563B	24	Y2	AY		9-8	SPARE	D04115P	B04			D43345P	B04			YL955-YL999, YN236-YN260
2563B	24	Y2	AY		9-8	MULTI	D04115P	B04			D43345P	B04			YN231-YN235
2563R	24	Y2	AY		0-0	23-27-39	D04115P	A04			D43345P	A04			YL951-YL954
2563R	24	Y2	AY		0-0	SPARE	D04115P	A04			D43345P	A04			YL955-YL999, YN236-YN260
2563R	24	Y2	AY		0-0	MULTI	D04115P	A04			D43345P	A04			YN231-YN235
2563Z			AY		0-0	23-27-39	D04115P	PERG	1F		D43345P	PERG	1F		YL951-YL954
2563Z			AY		0-0	SPARE	D04115P	PERG	1F		D43345P	PERG	1F		YL955-YL999, YN236-YN260
2563Z			AY		0-0	MULTI	D04115P	PERG	1F		D43345P	PERG	1F		YN231-YN235
2564B	24	Y2	BE		9-8	23-27-39	D04115P	B05			D43345P	B05			YL951-YL954
2564B	24	Y2	BE		9-8	SPARE	D04115P	B05			D43345P	B05			YL955-YL999, YN236-YN260
2564B	24	Y2	BE		9-8	MULTI	D04115P	B05			D43345P	B05			YN231-YN235
2564R	24	Y2	BE		0-0	23-27-39	D04115P	A05			D43345P	A05			YL951-YL954
2564R	24	Y2	BE		0-0	SPARE	D04115P	A05			D43345P	A05			YL955-YL999, YN236-YN260
2564R	24	Y2	BE		0-0	MULTI	D04115P	A05			D43345P	A05			YN231-YN235
2564Z			BE		0-0	23-27-39	D04115P	PERG	1F		D43345P	PERG	1F		YL951-YL954

WIRE LIST

D280A108

91-21-11

Section W5330

Page 5

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5331	286A5331			CMU INTERFACES E3-3 (LEFT) (continued)											
2564Z				BE	0-0	SPARE	D04115P	PERG	1F		D43345P	PERG	1F		YL955-YL999, YN236-YN260
2564Z				BE	0-0	MULTI	D04115P	PERG	1F		D43345P	PERG	1F		YN231-YN235
2565B	24	Y2		BG	9-10	SPARE	D04117P		B04		D43347P		B04		YL951-YL999, YN236-YN260
2565B	24	Y2		BG	9-10	31-35-02	D04117P		B04		D43347P		B04		YN231-YN235
2565R	24	Y2		BG	0-0	SPARE	D04117P		A04		D43347P		A04		YL951-YL999, YN236-YN260
2565R	24	Y2		BG	0-0	31-35-02	D04117P		A04		D43347P		A04		YN231-YN235
2565Z				BG	0-0	SPARE	D04117P	PERG	1F		D43347P	PERG	1F		YL951-YL999, YN236-YN260
2565Z				BG	0-0	31-35-02	D04117P	PERG	1F		D43347P	PERG	1F		YN231-YN235
W5335	286A5335			CMU INTERFACES E3-3 (RIGHT)											
0001	22	PA			6-5	SPARE	D04007P		A01		D43379P		A01		YD158-YR328
0002	22	PA			6-5	23-27-31	D04007P		B01		D43379P		B01		YD158-YR328
0003	22	PA			6-5	SPARE	D04007P		A02		D43379P		A02		YD158-YR328
0004	22	PA			6-5	SPARE	D04007P		B02		D43379P		B02		YD158-YR328
2501B	24	Y2	AA		6-5	23-27-37	D04007P		B08		D43379P		B08		YD158-YR328
2501R	24	Y2	AA		0-0	23-27-37	D04007P		A08		D43379P		A08		YD158-YR328
2501Z			AA		0-0	23-27-37	D04007P	PERG	1F		D43379P	PERG	1F		YD158-YR328
2502B	24	Y2	AB		6-5	23-27-37	D04007P		B09		D43379P		B09		YD158-YR328
2502R	24	Y2	AB		0-0	23-27-37	D04007P		A09		D43379P		A09		YD158-YR328
2502Z			AB		0-0	23-27-37	D04007P	PERG	1F		D43379P	PERG	1F		YD158-YR328
2503B	24	Y2	AC		6-5	SPARE	D04007P		B10		D43379P		B10		YD158-YR328
2503R	24	Y2	AC		0-0	SPARE	D04007P		A10		D43379P		A10		YD158-YR328
2503Z			AC		0-0	SPARE	D04007P	PERG	1F		D43379P	PERG	1F		YD158-YR328
2504B	24	Y2	AD		6-5	MULTI	D04009P		B01		D43379P		B11		YD158-YD170
2504B	24	Y2	AD		6-5	31-62-25	D04009P		B01		D43379P		B11		YL951-YN260
2504B	24	Y2	AD		6-5	SPARE	D04009P		B01		D43379P		B11		YN501-YR328
2504R	24	Y2	AD		0-0	MULTI	D04009P		A01		D43379P		A11		YD158-YD170
2504R	24	Y2	AD		0-0	31-62-25	D04009P		A01		D43379P		A11		YL951-YN260
2504R	24	Y2	AD		0-0	SPARE	D04009P		A01		D43379P		A11		YN501-YR328
2504Z			AD		0-0	MULTI	D04009P	PERG	1F		D43379P	PERG	1F		YD158-YD170
2504Z			AD		0-0	31-62-25	D04009P	PERG	1F		D43379P	PERG	1F		YL951-YN260
2504Z			AD		0-0	SPARE	D04009P	PERG	1F		D43379P	PERG	1F		YN501-YR328
2505B	24	Y2	AE		6-5	34-61-23	D04009P		B02		D43379P		B12		YD158-YR328
2505R	24	Y2	AE		0-0	34-61-23	D04009P		A02		D43379P		A12		YD158-YR328
2505Z			AE		0-0	34-61-23	D04009P	PERG	1F		D43379P	PERG	1F		YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W5330

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5335	286A5335				CMU INTERFACES E3-3 (RIGHT) (continued)											
2506B	24	Y2	AF		6-5	34-61-25		D04009P	B03			D43379P	B13			YD158-YN260
2506B	24	Y2	AF		6-5	SPARE		D04009P	B03			D43379P	B13			YN501-YR328
2506R	24	Y2	AF		0-0	34-61-25		D04009P	A03			D43379P	A13			YD158-YN260
2506R	24	Y2	AF		0-0	SPARE		D04009P	A03			D43379P	A13			YN501-YR328
2506Z			AF		0-0	34-61-25		D04009P	PERG	1F		D43379P	PERG	1F		YD158-YN260
2506Z			AF		0-0	SPARE		D04009P	PERG	1F		D43379P	PERG	1F		YN501-YR328
2507B	24	Y2	AG		6-5	34-61-25		D04009P	B04			D43379P	B14			YD158-YN260
2507B	24	Y2	AG		6-5	SPARE		D04009P	B04			D43379P	B14			YN501-YR328
2507R	24	Y2	AG		0-0	34-61-25		D04009P	A04			D43379P	A14			YD158-YN260
2507R	24	Y2	AG		0-0	SPARE		D04009P	A04			D43379P	A14			YN501-YR328
2507Z			AG		0-0	34-61-25		D04009P	PERG	1F		D43379P	PERG	1F		YD158-YN260
2507Z			AG		0-0	SPARE		D04009P	PERG	1F		D43379P	PERG	1F		YN501-YR328
2508B	24	Y2	AH		6-5	34-61-25		D04009P	B05			D43379P	B15			YD158-YN260
2508B	24	Y2	AH		6-5	SPARE		D04009P	B05			D43379P	B15			YN501-YR328
2508R	24	Y2	AH		0-0	34-61-25		D04009P	A05			D43379P	A15			YD158-YN260
2508R	24	Y2	AH		0-0	SPARE		D04009P	A05			D43379P	A15			YN501-YR328
2508Z			AH		0-0	34-61-25		D04009P	PERG	1F		D43379P	PERG	1F		YD158-YN260
2508Z			AH		0-0	SPARE		D04009P	PERG	1F		D43379P	PERG	1F		YN501-YR328
2509B	24	Y2	AI		6-5	34-61-21		D04009P	B06			D43379P	B16			YD158-YR328
2509R	24	Y2	AI		0-0	34-61-21		D04009P	A06			D43379P	A16			YD158-YR328
2509Z			AI		0-0	34-61-21		D04009P	PERG	1F		D43379P	PERG	1F		YD158-YR328
2510B	24	Y2	AJ		6-5	SPARE		D04007P	B07			D43379P	B07			YD158-YR328
2510R	24	Y2	AJ		0-0	SPARE		D04007P	A07			D43379P	A07			YD158-YR328
2510Z			AJ		0-0	SPARE		D04007P	PERG	1F		D43379P	PERG	1F		YD158-YR328
2511B	24	Y2	AK		6-5	34-45-21		D04009P	B07			D43379P	B17			YD158-YR328
2511R	24	Y2	AK		0-0	34-45-21		D04009P	A07			D43379P	A17			YD158-YR328
2511Z			AK		0-0	34-45-21		D04009P	PERG	1F		D43379P	PERG	1F		YD158-YR328
2513B	24	Y2	AQ		6-5	23-27-36		D04009P	B08			D43379P	B18			YD158-YD170, YN501-YR328
2513B	24	Y2	AQ		6-5	SPARE		D04009P	B08			D43379P	B18			YL951-YN260
2513R	24	Y2	AQ		0-0	23-27-36		D04009P	A08			D43379P	A18			YD158-YD170, YN501-YR328
2513R	24	Y2	AQ		0-0	SPARE		D04009P	A08			D43379P	A18			YL951-YN260
2513Z			AQ		0-0	23-27-36		D04009P	PERG	1F		D43379P	PERG	1F		YD158-YD170, YN501-YR328
2513Z			AQ		0-0	SPARE		D04009P	PERG	1F		D43379P	PERG	1F		YL951-YN260
2561B	24	Y2	OK		6-5	23-27-37		D43379P	B03			D04007P	B03			YD158-YR328
2561R	24	Y2	OK		0-0	23-27-37		D43379P	A03			D04007P	A03			YD158-YR328
2561Z			OK		0-0	23-27-37		D43379P	PERG	1F		D04007P	PERG	1F		YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W5330

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram		From				To				Effectivity
	GA	CO	TY		FT-IN		Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W5335	286A5335			CMU INTERFACES E3-3 (RIGHT) (continued)											
2562B	24	Y2	OL	6-5	23-27-33	D43379P	B20				D04009P	B10			YD158-YR328
2562R	24	Y2	OL	0-0	23-27-33	D43379P	A20				D04009P	A10			YD158-YR328
2562Z			OL	0-0	23-27-33	D43379P	PERG	1F			D04009P	PERG	1F		YD158-YR328
2566B	24	M5	OP	6-5	SPARE	D43379P	B06				D04007P	B06			YD158-YR328
2566R	24	M5	OP	0-0	SPARE	D43379P	A06				D04007P	A06			YD158-YR328
2566ZI			OP	0-0	SPARE	D43379P	A05				D04007P	A05			YD158-YR328
2566ZO			OP	0-0	SPARE	D43379P	PERG	1F			D04007P	PERG	1F		YD158-YR328
2567B	24	Y2	OQ	6-5	23-27-33	D43379P	B19				D04009P	B09			YD158-YD170, YL965-YL970, YN236-YN260
2567B	24	Y2	OQ	6-5	MULTI	D43379P	B19				D04009P	B09			YL951-YL964, YL971-YN235
2567B	24	Y2	OQ	6-5	SPARE	D43379P	B19				D04009P	B09			YN501-YR328
2567R	24	Y2	OQ	0-0	23-27-33	D43379P	A19				D04009P	A09			YD158-YD170, YL965-YL970, YN236-YN260
2567R	24	Y2	OQ	0-0	MULTI	D43379P	A19				D04009P	A09			YL951-YL964, YL971-YN235
2567R	24	Y2	OQ	0-0	SPARE	D43379P	A19				D04009P	A09			YN501-YR328
2567Z			OQ	0-0	23-27-33	D43379P	PERG	1F			D04009P	PERG	1F		YD158-YD170, YL965-YL970, YN236-YN260
2567Z			OQ	0-0	MULTI	D43379P	PERG	1F			D04009P	PERG	1F		YL951-YL964, YL971-YN235
2567Z			OQ	0-0	SPARE	D43379P	PERG	1F			D04009P	PERG	1F		YN501-YR328
W5337	286A5337			SERVICE INTERPHONE, TB205, E RACK, P19											
0001	22	PA		22-2	SPARE	D04161P	A07				D04499P	1			YC051-YC055
0001	22	PA		22-6	SPARE	D04161P	A07				D04499P	1			YC056-YL954, YN231-YN235
0001	22	PA		21-9	SPARE	D04161P	A07				D40664	24			YL955-YL999, YN236, YN501-YR328
0002	22	CQ		8-3	34-21-22	S01127	6	C			GD01008	DC..	1A		YL951-YN236, YN501-YR328
0003	22	CQ		22-0	34-21-22	S01127	5	C			D04161P	A06			YL951-YN236, YN501-YR328
0004	22	PA		8-3	34-21-12	S01127	3	C			GD01008	DC..	1A		YL951-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W5330

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description		From				To				Effectivity	
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type		Splice
W5337	286A5337			SERVICE INTERPHONE, TB205, E RACK, P19 (continued)											
0005	22	PA			22-0	34-21-12	S01127	2	C		D04161P	B06			YL951-YN236, YN501-YR328
2201B	22	PB	AF		22-2	24-41-11	D04161P	A10			D04499P	4			YC051-YC055
2201B	22	PB	AF		22-6	24-41-11	D04161P	A10			D04499P	4			YC056-YL954, YN231-YN235
2201B	22	PB	AF		21-9	24-41-11	D04161P	A10			D40664	25			YL955-YL999, YN236, YN501-YR328
2201R	22	PB	AF		0-0	24-41-11	D04161P	A09			D04499P	3			YC051-YL954, YN231-YN235
2201R	22	PB	AF		0-0	24-41-11	D04161P	A09			D40664	26			YL955-YL999, YN236, YN501-YR328
2202B	22	PB	AG		22-5	24-41-11	D04161P	B10			D00048	F	E		YC051-YC055
2202B	22	PB	AG		22-9	24-41-11	D04161P	B10			D00048	F	E		YC056-YL954, YN231-YN235
2202B	22	PB	AG		22-3	24-41-11	D04161P	B10			D00048	F	E		YL955-YL999, YN236, YN501-YR312
2202B	22	PB	AG		22-10	24-41-11	D04161P	B10			D00048	F	E		YR313-YR328
2202R	22	PB	AG		0-0	24-41-11	D04161P	B09			D00048	E	E		YC051-YN236, YN501-YR328
3501B	24	Y3	AA		34-7	23-41-11	D04161P	A02			TB0205W	B001	1		YC051-YC055
3501B	24	Y3	AA		34-10	23-41-11	D04161P	A02			TB0205W	B001	1		YC056-YL999, YR301-YR328
3501B	24	Y3	AA		24-8	23-41-11	D04161P	A02			TB0205W	B001	1		YN231-YN236, YN501
3501R	24	Y3	AA		0-0	23-41-11	D04161P	A01			TB0205W	A001	1		YC051-YN236, YN501-YR328
3501Y	24	Y3	AA		0-0	23-41-11	D04161P	B01			TB0205W	A005	1		YC051-YN236, YN501-YR328
3501Z			AA		0-0	23-41-11	D04161P			AA	TB0205W	B005	1		YC051-YN236, YN501-YR328
3502B	22	X3	AB		11-4	23-41-11	D04161P	B03			SM00002		S		YC051-YC055
3502B	22	X3	AB		11-2	23-41-11	D04161P	B03			SM00002		S		YC056-YN236, YN501-YR328
3502R	22	X3	AB		0-0	23-41-11	D04161P	B02			SM00001		S		YC051-YN236, YN501-YR328
3502Y	22	X3	AB		0-0	23-41-11	D04161P	A03			SM00003		S		YC051-YN236, YN501-YR328
3502Z			AB		0-0	23-41-11	D04161P			AA	SM00004		S		YC051-YN236, YN501-YR328
3503B	20	X3	AC		22-2	23-41-11	D04161P	A05			D04499P	8			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5330

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5337	286A5337			SERVICE INTERPHONE, TB205, E RACK, P19 (continued)											
3503B	20	X3	AC		22-6	23-41-11	D04161P	A05			D04499P	8			YC056-YL954, YN231-YN235
3503B	20	X3	AC		21-9	23-41-11	D04161P	A05			D40664	29			YL955-YL999, YN236, YN501-YR328
3503R	20	X3	AC		0-0	23-41-11	D04161P	A04			D04499P	7			YC051-YL954, YN231-YN235
3503R	20	X3	AC		0-0	23-41-11	D04161P	A04			D40664	28			YL955-YL999, YN236, YN501-YR328
3503Y	20	X3	AC		0-0	23-41-11	D04161P	B04			D04499P	9			YC051-YL954, YN231-YN235
3503Y	20	X3	AC		0-0	23-41-11	D04161P	B04			D40664	30			YL955-YL999, YN236, YN501-YR328
3503Z			AC		0-0	23-41-11	D04161P			AA	D04499P	DED			YC051-YL954, YN231-YN235
3503Z			AC		0-0	23-41-11	D04161P			AA	D40664	DED			YL955-YL999, YN236, YN501-YR328
3504B	22	X3	AD		13-3	23-41-11	SM00002		S		D04499P	11			YC051-YC055
3504B	22	X3	AD		13-11	23-41-11	SM00002		S		D04499P	11			YC056-YL954, YN231-YN235
3504B	22	X3	AD		13-2	23-41-11	SM00002		S		D40664	32			YL955-YL999, YR301-YR328
3504B	22	X3	AD		13-3	23-41-11	SM00002		S		D40664	32			YN236, YN501
3504R	22	X3	AD		0-0	23-41-11	SM00001		S		D04499P	10			YC051-YL954, YN231-YN235
3504R	22	X3	AD		0-0	23-41-11	SM00001		S		D40664	31			YL955-YL999, YN236, YN501-YR328
3504Y	22	X3	AD		0-0	23-41-11	SM00003		S		D04499P	12			YC051-YL954, YN231-YN235
3504Y	22	X3	AD		0-0	23-41-11	SM00003		S		D40664	33			YL955-YL999, YN236, YN501-YR328
3504Z			AD		0-0	23-41-11	SM00004		S		D04499P	DED			YC051-YL954, YN231-YN235
3504Z			AD		0-0	23-41-11	SM00004		S		D40664	DED			YL955-YL999, YN236, YN501-YR328
3505B	22	X3	AE		11-5	23-41-11	SM00002		S		SM00007		S		YC051-YD170
3505B	22	X3	AE		11-1	23-41-11	SM00002		S		SM00007		S		YL951-YL999, YR301-YR328
3505B	22	X3	AE		11-6	23-41-11	SM00002		S		SM00007		S		YN231-YN236, YN501

WIRE LIST

D280A108

91-21-11

Section W5330

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To				Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type		Splice
W5337	286A5337				SERVICE INTERPHONE, TB205, E RACK, P19 (continued)										
3505R	22	X3	AE	0-0	23-41-11	SM00001		S		SM00005		S		YC051-YN236, YN501-YR328	
3505Y	22	X3	AE	0-0	23-41-11	SM00003		S		SM00009		S		YC051-YN236, YN501-YR328	
3505Z			AE	0-0	23-41-11	SM00004		S		SM00005	DED			YC051-YN236, YN501-YR328	
A-A				0-0	23-41-11	SM00005		S		D06025	RED			YC051-YN236, YN501-YR328	
A-B				0-0	23-41-11	SM00007		S		D06025	BLU			YC051-YN236, YN501-YR328	
A-C				0-0	23-41-11	SM00009		S		D06025	BLK			YC051-YN236, YN501-YR328	
FRAA				0-0	23-41-11	D04161P			AA	D04161P	B05			YC051-YN236, YN501-YR328	

WIRE LIST
D280A108

91-21-11
Section W5330
Page 11 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5353 286A5353 AUTOTHROTTLE SERVO MOTOR 1 TO E1-1																
0001	22			PA		1-2	22-31-31	D10025			AA	GD01835	ST..	E		ALL
0002	22			PA		1-1	22-31-31	D10025	10			GD01836	DC..	E		ALL
0003	22			PA		0-7	22-31-31	D10025	5			D10025	1			ALL
0004	22			PA		1-2	22-31-31	D10025			AD	GD01835	ST..	E		ALL
2001B	22			PB	AC	14-10	22-31-31	D10025	3			D41159P	B03			ALL
2001R	22			PB	AC	0-0	22-31-31	D10025	9			D41159P	A03			ALL
2002B	24			PL	AB	14-10	22-31-31	D10025	6			D41159P	B02			ALL
2002R	24			PL	AB	0-0	22-31-31	D10025	14			D41159P	A02			ALL
2501B	24			Y2	AA	14-10	22-31-31	D10025	8			D41159P	B01			ALL
2501R	24			Y2	AA	0-0	22-31-31	D10025	7			D41159P	A01			ALL
2501Z					AA	0-0	22-31-31	D10025			AA	D41159P	PERG	1F		ALL
2504B	24			Y2	AD	14-10	22-31-31	D10025	13			D41159P	B04			ALL
2504R	24			Y2	AD	0-0	22-31-31	D10025	12			D41159P	A04			ALL
2504Z					AD	0-0	22-31-31	D10025			AD	D41159P	PERG	1F		ALL
W5355 286A5355 INTERPHONE - L WHEEL WELL																
3501B	20			X3	AA	25-11	23-41-11	TB0205W	B001	1		SM00003		9		YC051-YD152
3501B	20			X3	AA	26-5	23-41-11	TB0205W	B001	1		SM00003		9		YD153-YR328
3501R	20			X3	AA	0-0	23-41-11	TB0205W	A001	1		SM00001		9		ALL
3501Y	20			X3	AA	0-0	23-41-11	TB0205W	A005	1		SM00005		9		ALL
3501Z					AA	0-0	23-41-11	TB0205W	B005	1		SM00001	DED			ALL
A-A						0-0	23-41-11	SM00001		9		D06011	RED			ALL
A-B						0-0	23-41-11	SM00003		9		D06011	BLU			ALL
A-C						0-0	23-41-11	SM00005		9		D06011	BLK			ALL
W5357 286A5357 INTERPHONE - RIGHT WHEEL WELL																
3501B	20			X3	AA	20-0	23-41-11	TB0205W	B001	1		SM00003		9		YC051-YD158, YL951-YL963, YN231-YN235
3501B	20			X3	AA	19-11	23-41-11	TB0205W	B001	1		SM00003		9		YL964-YL999, YN236-YR323, YR325-YR328
3501R	20			X3	AA	0-0	23-41-11	TB0205W	A001	1		SM00001		9		YC051-YD158, YL951-YR323, YR325-YR328
3501Y	20			X3	AA	0-0	23-41-11	TB0205W	A005	1		SM00005		9		YC051-YD158, YL951-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W5350

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5357	286A5357			INTERPHONE - RIGHT WHEEL WELL (continued)											
3501Z				AA	0-0	23-41-11	TB0205W	B005	1		SM00001	DED			YC051-YD158, YL951-YR323, YR325-YR328
A-A					0-0	23-41-11	SM00001		9		D06057	RED			YC051-YD158, YL951-YR323, YR325-YR328
A-B					0-0	23-41-11	SM00003		9		D06057	BLU			YC051-YD158, YL951-YR323, YR325-YR328
A-C					0-0	23-41-11	SM00005		9		D06057	BLK			YC051-YD158, YL951-YR323, YR325-YR328

WIRE LIST
D280A108

91-21-11
Section W5350
Page 2 End
Nov 12/2012



WIRE LIST
D280A108

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5367	286A5367			AUTOPILOT E1-1 TO ACCEL PCU SYSTEM - A (continued)											
2003B	22	HB	AC		1-2	22-11-31	D01827	10			SM00003		9		YD153-YN236, YN501-YR328
2003R	22	HB	AC		0-0	22-11-31	D01827	9			SM00001		9		YC051-YN236, YN501-YR328
2005B	22	PB	AE		64-10	22-11-31	D04073P	A05			D42102J		2		YC051-YD152
2005B	22	PB	AE		65-0	22-11-31	D04073P	A05			D42102J		2		YD153-YL999, YR301-YR328
2005B	22	PB	AE		55-2	22-11-31	D04073P	A05			D42102J		2		YN231-YN236, YN501
2005R	22	PB	AE		0-0	22-11-31	D04073P	A04			D42102J		1		YC051-YN236, YN501-YR328
2007B	22	PB	AG		68-11	22-11-31	D04073P	A07			D43100J		4		YC051-YC055
2007B	22	PB	AG		69-0	22-11-31	D04073P	A07			D43100J		4		YC056-YD152
2007B	22	PB	AG		69-1	22-11-31	D04073P	A07			D43100J		4		YD153-YL999, YR301-YR328
2007B	22	PB	AG		59-3	22-11-31	D04073P	A07			D43100J		4		YN231-YN236, YN501
2007R	22	PB	AG		0-0	22-11-31	D04073P	A06			D43100J		3		YC051-YN236, YN501-YR328
2008B	20	HB	AH		61-11	22-11-31	D04073P	B20			D01827		1		YC051-YC055
2008B	20	HB	AH		61-10	22-11-31	D04073P	B20			D01827		1		YC056-YD152
2008B	20	HB	AH		62-4	22-11-31	D04073P	B20			D01827		1		YD153-YL999, YR301-YR328
2008B	20	HB	AH		52-6	22-11-31	D04073P	B20			D01827		1		YN231-YN236, YN501
2008R	20	HB	AH		0-0	22-11-31	D04073P	B19			D01827		21		YC051-YN236, YN501-YR328
2009B	22	HB	AI		61-11	22-11-31	D04073P	A09			D01827		8		YC051-YC055
2009B	22	HB	AI		61-10	22-11-31	D04073P	A09			D01827		8		YC056-YD152
2009B	22	HB	AI		62-4	22-11-31	D04073P	A09			D01827		8		YD153-YL999, YR301-YR328
2009B	22	HB	AI		52-6	22-11-31	D04073P	A09			D01827		8		YN231-YN236, YN501
2009R	22	HB	AI		0-0	22-11-31	D04073P	A08			D01827		5		YC051-YN236, YN501-YR328
2010B	22	PB	AJ		58-7	27-18-11	D43100J	2			D40053P	A02			YC051-YC055
2010B	22	PB	AJ		58-8	27-18-11	D43100J	2			D40053P	A02			YC056-YD152
2010B	22	PB	AJ		58-9	27-18-11	D43100J	2			D40053P	A02			YD153-YL999, YR301-YR328
2010B	22	PB	AJ		48-5	27-18-11	D43100J	2			D40053P	A02			YN231-YN236, YN501
2010R	22	PB	AJ		0-0	27-18-11	D43100J	1			D40053P	A01			YC051-YN236, YN501-YR328
2011B	22	PB	AK		58-7	27-62-14	D43100J	12			D40053P	A04			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5360

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5367	286A5367			AUTOPILOT E1-1 TO ACCEL PCU SYSTEM - A (continued)											
2011B	22	PB	AK		58-8	27-62-14	D43100J	12			D40053P	A04			YC056-YD152
2011B	22	PB	AK		58-9	27-62-14	D43100J	12			D40053P	A04			YD153-YL999, YR301-YR328
2011B	22	PB	AK		48-5	27-62-14	D43100J	12			D40053P	A04			YN231-YN236, YN501
2011R	22	PB	AK		0-0	27-62-14	D43100J	11			D40053P	A03			YC051-YN236, YN501-YR328
2015B	22	X2	AP		64-10	22-11-11	D04073P	A11			D42102J	4			YC051-YD152
2015B	22	X2	AP		65-0	22-11-11	D04073P	A11			D42102J	4			YD153-YL999, YR301-YR328
2015B	22	X2	AP		55-2	22-11-11	D04073P	A11			D42102J	4			YN231-YN236, YN501
2015R	22	X2	AP		0-0	22-11-11	D04073P	A10			D42102J	3			YC051-YN236, YN501-YR328
2015Z			AP		0-0	22-11-11	D04073P	DED			D42102J	DED			YC051-YC055
2015Z			AP		0-0	22-11-11	D04073P	PERG	1F		D42102J	S/R			YC056-YN236, YN501-YR328
2017B	22	PB	AS		61-5	22-11-31	D04073P	B13			SM00003		9		YC051-YC055
2017B	22	PB	AS		61-4	22-11-31	D04073P	B13			SM00003		9		YC056-YD152
2017B	22	PB	AS		61-9	22-11-31	D04073P	B13			SM00003		9		YD153-YL999, YR301-YR328
2017B	22	PB	AS		51-11	22-11-31	D04073P	B13			SM00003		9		YN231-YN236, YN501
2017R	22	PB	AS		0-0	22-11-31	D04073P	B12			SM00001		9		YC051-YN236, YN501-YR328
2018B	20	X2	OS		63-9	27-62-11	D43100J	30			D43910P	2			YL953-YL999, YR301-YR328
2018R	20	X2	OS		0-0	27-62-11	D43100J	29			D43910P	1			YL953-YL999, YR301-YR328
2018Z			OS		0-0	27-62-11	D43100J	S/R			D43910P	PERS	1A		YL953-YL999, YR301-YR328
2019B	20	X2	OT		63-9	27-62-11	D43100J	32			D43910P	4			YL953-YL999, YR301-YR328
2019R	20	X2	OT		0-0	27-62-11	D43100J	31			D43910P	3			YL953-YL999, YR301-YR328
2019Z			OT		0-0	27-62-11	D43100J	S/R			D43910P	PERS	1A		YL953-YL999, YR301-YR328
2020B	20	X2	OU		63-9	27-62-11	D43100J	34			D43910P	6			YL953-YL999, YR301-YR328
2020R	20	X2	OU		0-0	27-62-11	D43100J	33			D43910P	5			YL953-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W5360

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5367	286A5367			AUTOPILOT E1-1 TO ACCEL PCU SYSTEM - A (continued)											
2020Z				OU	0-0	27-62-11	D43100J	S/R			D43910P	PERS	1A		YL953-YL999, YR301-YR328
2021B	20	X2	OV		63-9	27-62-11	D43100J	36			D43910P	8			YL953-YL999, YR301-YR328
2021R	20	X2	OV		0-0	27-62-11	D43100J	35			D43910P	7			YL953-YL999, YR301-YR328
2021Z				OV	0-0	27-62-11	D43100J	S/R			D43910P	PERS	1A		YL953-YL999, YR301-YR328
3001B	22	PC	BA		63-5	22-11-31	D04073P	A13			D01709	5			YC051-YC055
3001B	22	PC	BA		63-7	22-11-31	D04073P	A13			D01709	5			YC056-YD152
3001B	22	PC	BA		62-11	22-11-31	D04073P	A13			D01709	5			YD153-YL999, YR301-YR328
3001B	22	PC	BA		53-1	22-11-31	D04073P	A13			D01709	5			YN231-YN236, YN501
3001R	22	PC	BA		0-0	22-11-31	D04073P	A12			D01709	4			YC051-YN236, YN501-YR328
3001Y	22	PC	BA		0-0	22-11-31	D04073P	A14			D01709	3			YC051-YN236, YN501-YR328
3002B	22	X3	BB		58-7	27-32-11	D43100J	25			D40053P	B05			YC051-YC055
3002B	22	X3	BB		58-8	27-32-11	D43100J	25			D40053P	B05			YC056-YD152
3002B	22	X3	BB		58-9	27-32-11	D43100J	25			D40053P	B05			YD153-YL999, YR301-YR328
3002B	22	X3	BB		48-5	27-32-11	D43100J	25			D40053P	B05			YN231-YN236, YN501
3002R	22	X3	BB		0-0	27-32-11	D43100J	24			D40053P	B04			YC051-YN236, YN501-YR328
3002Y	22	X3	BB		0-0	27-32-11	D43100J	26			D40053P	B06			YC051-YN236, YN501-YR328
3002Z				BB	0-0	27-32-11	D43100J	DED			D40053P	DED			YC051-YN236, YN501-YR328
3004B	22	HC	BD		61-11	22-11-31	D04073P	A16			D01827	12			YC051-YC055
3004B	22	HC	BD		61-10	22-11-31	D04073P	A16			D01827	12			YC056-YD152
3004B	22	HC	BD		62-4	22-11-31	D04073P	A16			D01827	12			YD153-YL999, YR301-YR328
3004B	22	HC	BD		52-6	22-11-31	D04073P	A16			D01827	12			YN231-YN236, YN501
3004R	22	HC	BD		0-0	22-11-31	D04073P	A15			D01827	11			YC051-YN236, YN501-YR328
3004Y	22	HC	BD		0-0	22-11-31	D04073P	A17			D01827	13			YC051-YN236, YN501-YR328
3007B	22	X3	BG		64-10	22-12-31	D04073P	A19			D42102J	9			YC051-YD152

WIRE LIST

D280A108

91-21-11

Section W5360

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5367	286A5367			AUTOPILOT E1-1 TO ACCEL PCU SYSTEM - A (continued)											
3007B	22	X3	BG		65-0	22-12-31	D04073P	A19			D42102J	9			YD153-YL999, YR301-YR328
3007B	22	X3	BG		55-2	22-12-31	D04073P	A19			D42102J	9			YN231-YN236, YN501
3007R	22	X3	BG		0-0	22-12-31	D04073P	A18			D42102J	8			YC051-YN236, YN501-YR328
3007Y	22	X3	BG		0-0	22-12-31	D04073P	A20			D42102J	10			YC051-YN236, YN501-YR328
3007Z			BG		0-0	22-12-31	D04073P	PERG	1F		D42102J	S/R			YC051-YN236, YN501-YR328
3011B	22	PC	DA		58-7	27-62-14	D43100J	17			D40053P	B02			YC051-YC055
3011B	22	PC	DA		58-8	27-62-14	D43100J	17			D40053P	B02			YC056-YD152
3011B	22	PC	DA		58-9	27-62-14	D43100J	17			D40053P	B02			YD153-YL999, YR301-YR328
3011B	22	PC	DA		48-5	27-62-14	D43100J	17			D40053P	B02			YN231-YN236, YN501
3011R	22	PC	DA		0-0	27-62-14	D43100J	16			D40053P	B01			YC051-YN236, YN501-YR328
3011Y	22	PC	DA		0-0	27-62-14	D43100J	18			D40053P	B03			YC051-YN236, YN501-YR328
3013B	22	HG	BM		61-11	SPARE	D04073P	B02			D01827	REF	VP		YC051-YC055
3013B	22	HG	BM		61-10	SPARE	D04073P	B02			D01827	REF	VP		YC056-YD152
3013B	22	HG	BM		62-4	SPARE	D04073P	B02			D01827	REF	VP		YD153-YL999, YR301-YR328
3013B	22	HG	BM		52-6	SPARE	D04073P	B02			D01827	REF	VP		YN231-YN236, YN501
3013R	22	HG	BM		0-0	SPARE	D04073P	B01			D01827	REF	VP		YC051-YN236, YN501-YR328
3013Y	22	HG	BM		0-0	SPARE	D04073P	B03			D01827	REF	VP		YC051-YN236, YN501-YR328
3013Z			BM		0-0	SPARE	D04073P	PERG	1F		D01827	DED			YC051-YN236, YN501-YR328
3015B	22	PC	BP		58-7	27-18-11	D43100J	6			D40053P	A06			YC051-YC055
3015B	22	PC	BP		58-8	27-18-11	D43100J	6			D40053P	A06			YC056-YD152
3015B	22	PC	BP		58-9	27-18-11	D43100J	6			D40053P	A06			YD153-YL999, YR301-YR328
3015B	22	PC	BP		48-5	27-18-11	D43100J	6			D40053P	A06			YN231-YN236, YN501
3015R	22	PC	BP		0-0	27-18-11	D43100J	5			D40053P	A05			YC051-YN236, YN501-YR328
3015Y	22	PC	BP		0-0	27-18-11	D43100J	7			D40053P	A07			YC051-YN236, YN501-YR328
3016B	22	PC	BR		64-10	22-11-31	D04073P	B05			D42102J	6			YC051-YD152

WIRE LIST

D280A108

91-21-11

Section W5360

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5367	286A5367			AUTOPILOT E1-1 TO ACCEL PCU SYSTEM - A (continued)											
3016B	22	PC	BR		65-0	22-11-31	D04073P	B05			D42102J	6			YD153-YL999, YR301-YR314
3016B	22	PC	BR		55-2	22-11-31	D04073P	B05			D42102J	6			YN231-YN236, YN501
3016B	22	PB	BR		65-0	22-11-31	D04073P	B05			D42102J	6			YR315-YR328
3016R	22	PC	BR		0-0	22-11-31	D04073P	B04			D42102J	5			YC051-YN236, YN501-YR314
3016R	22	PB	BR		0-0	22-11-31	D04073P	B04			D42102J	5			YR315-YR328
3016Y	22	PC	BR		0-0	22-11-31	D04073P	B06			D42102J	7			YC051-YN236, YN501-YR314
3019B	22	PC	BU		68-11	22-11-31	D04073P	B08			D43100J	9			YC051-YC055
3019B	22	PC	BU		69-0	22-11-31	D04073P	B08			D43100J	9			YC056-YD152
3019B	22	PC	BU		69-1	22-11-31	D04073P	B08			D43100J	9			YD153-YL999, YR301-YR314
3019B	22	PC	BU		59-3	22-11-31	D04073P	B08			D43100J	9			YN231-YN236, YN501
3019B	22	PB	BU		69-1	22-11-31	D04073P	B08			D43100J	9			YR315-YR328
3019R	22	PC	BU		0-0	22-11-31	D04073P	B07			D43100J	8			YC051-YN236, YN501-YR314
3019R	22	PB	BU		0-0	22-11-31	D04073P	B07			D43100J	8			YR315-YR328
3019Y	22	PC	BU		0-0	22-11-31	D04073P	B09			D43100J	10			YC051-YN236, YN501-YR314
W5369	286A5369			AUTOPILOT E1-1 TO ELEX PANEL AND TB803 - SYSTEM A											
0001	20	PA			1-8	22-11-11	D00385	5			GD01041	ST..	E		YC051-YC064
0001	20	PA			2-1	22-11-11	D00385	5			GD01041	ST..	E		YC065-YR328
0003	20	PA			21-10	22-11-12	D04075P	A03			TB0805Y	A009	1A		YC051-YC064
0003	20	PA			21-8	22-11-12	D04075P	A03			TB0805Y	A009	1A		YC065-YR328
0004	20	PA			13-1	22-11-12	D04075P	A04			TB0806X	B013	1A		ALL
0005	22	PA			14-3	22-11-14	D04075P	A05			SM00001		S		YC051-YC052
0005	22	PA			14-1	22-11-14	D04075P	A05			SM00001		S		YC053-YC064
0005	22	PA			14-9	22-11-14	D04075P	A05			SM00001		S		YC065-YR328
0006	22	PA			14-3	22-11-14	D04075P	A06			SM00003		S		YC051-YC052
0006	22	PA			14-1	22-11-14	D04075P	A06			SM00003		S		YC053-YC064
0006	22	PA			14-9	22-11-14	D04075P	A06			SM00003		S		YC065-YR328
0011	20	CQ			12-2	22-13-11	D02257	23			D00417	2			YC051-YC064
0011	20	CQ			11-9	22-13-11	D02257	23			D00417	2			YC065-YR328
0012	20	PA			12-2	22-13-11	D02257	12			D00417	12			YC051-YC064
0012	20	PA			11-9	22-13-11	D02257	12			D00417	12			YC065-YR328
0013	20	PA			12-2	22-13-11	D02257	13			D00417	13			YC051-YC064
0013	20	PA			11-9	22-13-11	D02257	13			D00417	13			YC065-YR328

WIRE LIST

D280A108

91-21-11

Section W5360

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5369		286A5369					AUTOPILOT E1-1 TO ELEX PANEL AND TB803 - SYSTEM A (continued)								
	0014	20	PA		18-2	22-13-11	D02257		3		D04075P	A10			YC051-YC064
	0014	20	PA		17-9	22-13-11	D02257		3		D04075P	A10			YC065-YR328
	0015	20	PA		18-2	22-13-11	D02257		15		D04075P	A11			YC051-YC064
	0015	20	PA		17-9	22-13-11	D02257		15		D04075P	A11			YC065-YR328
	0016	20	PA		18-2	22-13-11	D02257		19		D04075P	A12			YC051-YC064
	0016	20	PA		17-9	22-13-11	D02257		19		D04075P	A12			YC065-YR328
	0017	20	CQ		18-2	22-13-11	D02257		22		D04075P	A13			YC051-YC064
	0017	20	CQ		17-9	22-13-11	D02257		22		D04075P	A13			YC065-YR328
	0018	20	CQ		18-2	22-13-11	D02257		16		D04075P	A14			YC051-YC064
	0018	20	CQ		17-9	22-13-11	D02257		16		D04075P	A14			YC065-YR328
	0019	20	CQ		18-2	22-13-11	D02257		24		D04075P	A15			YC051-YC064
	0019	20	CQ		17-9	22-13-11	D02257		24		D04075P	A15			YC065-YR328
	0020	20	CQ		18-2	22-13-11	D02257		14		D04075P	A16			YC051-YC064
	0020	20	CQ		17-9	22-13-11	D02257		14		D04075P	A16			YC065-YR328
	0021	20	CQ		3-6	22-13-11	D02257		8		GD00800	DC..	1A		YC051-YC064
	0021	20	CQ		3-4	22-13-11	D02257		8		GD00800	DC..	1A		YC065-YR328
	0022	20	CQ		3-6	22-13-11	D02257		9		GD00800	DC..	1A		YC051-YC064
	0022	20	CQ		3-4	22-13-11	D02257		9		GD00800	DC..	1A		YC065-YR328
	0023	20	CQ		3-6	22-13-11	D02257		20		GD00800	DC..	1A		YC051-YC064
	0023	20	CQ		3-4	22-13-11	D02257		20		GD00800	DC..	1A		YC065-YR328
	0025	20	PA		13-5	22-13-11	D00417		14		D04075P	A19			ALL
	0027	20	PA		13-5	22-13-11	D00417		15		D04075P	A20			ALL
	0028	20	PA		2-9	22-13-11	D00417		5		GD00809	DC..	1A		ALL
	0029	20	PA		13-5	22-13-11	D04075P		B01		D00417	9			ALL
	0030	20	PA		13-5	22-13-11	D04075P		B02		D00417	8			ALL
	0031	20	PA		2-9	22-13-11	D00417		6		GD00809	DC..	1A		ALL
	0032	20	PA		13-5	22-13-11	D04075P		B03		D00417	1			ALL
	0035	20	PA		1-5	22-11-11	D00383		5		GD00287	ST..	E		ALL
	0036	20	CQ		11-1	22-14-11	TB0805X		B016	1A	TB0806Y	B011	1A		YC051-YC064
	0036	20	CQ		10-11	22-14-11	TB0805X		B016	1A	TB0806Y	B011	1A		YC065-YR328
	0037	20	CQ		11-1	22-14-11	TB0805X		A016	1A	TB0806Y	A011	1A		YC051-YC064
	0037	20	CQ		10-11	22-14-11	TB0805X		A016	1A	TB0806Y	A011	1A		YC065-YR328
	0038	20	PA		11-2	22-11-12	TB0806X		A015	1A	TB0805X	B015	1A		YC051-YC064
	0038	20	PA		10-11	22-11-12	TB0806X		A015	1A	TB0805X	B015	1A		YC065-YR328
	0039	20	CQ		11-2	22-11-12	TB0805X		B014	1A	TB0806X	A014	1A		YC051-YC064
	0039	20	CQ		10-11	22-11-12	TB0805X		B014	1A	TB0806X	A014	1A		YC065-YR328
	0040	20	CQ		11-3	27-41-11	TB0805X		A001	1A	TB0806Y	A009	1A		YC051-YC064
	0040	20	CQ		11-1	27-41-11	TB0805X		A001	1A	TB0806Y	A009	1A		YC065-YR328
	0041	20	CQ		11-4	27-41-11	TB0805X		B001	1A	TB0806Z	A017	1A		YC051-YC064

WIRE LIST

D280A108

91-21-11

Section W5360

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5369	286A5369			AUTOPILOT E1-1 TO ELEX PANEL AND TB803 - SYSTEM A (continued)											
0041	20		CQ		11-2	27-41-11	TB0805X	B001	1A		TB0806Z	A017	1A		YC065-YR328
0042	20		CQ		11-4	27-41-11	TB0805X	A004	1A		TB0806Z	B017	1A		YC051-YC064
0042	20		CQ		11-2	27-41-11	TB0805X	A004	1A		TB0806Z	B017	1A		YC065-YR328
0043	20		CQ		11-5	27-41-11	TB0805X	B004	1A		TB0806Z	A021	1A		YC051-YC064
0043	20		CQ		11-2	27-41-11	TB0805X	B004	1A		TB0806Z	A021	1A		YC065-YR328
0044	20		CQ		11-1	33-14-11	TB0806Y	B009	1A		TB0805X	A013	1A		YC051-YC064
0044	20		CQ		10-11	33-14-11	TB0806Y	B009	1A		TB0805X	A013	1A		YC065-YR328
0045	20		PA		1-3	22-11-11	D00397		5		GD00289	ST..	E		ALL
0101	22		PA		1-1	22-11-14	SM00001			S	D08313P		1		YC051-YC052
0101	22		PA		1-2	22-11-14	SM00001			S	D08313P		1		YC053-YC064
0101	22		PA		0-7	22-11-14	SM00001			S	D08313P		1		YC065-YR328
0102	22		PA		1-1	22-11-14	SM00003			S	D08313P		2		YC051-YC052
0102	22		PA		1-2	22-11-14	SM00003			S	D08313P		2		YC053-YC064
0102	22		PA		0-7	22-11-14	SM00003			S	D08313P		2		YC065-YR328
0105	22		PA		14-9	22-31-51	D04075P		B15		D08313P		5		ALL
0106	22		PA		7-0	22-31-51	D08313P		6		SP03097			S	YC051-YC064
0106	22		PA		7-3	22-31-51	D08313P		6		SP03097			S	YC065-YR328
0107	22		PA		2-5	22-31-51	D08313P		7		GD00800	DC..	1A		YC051-YC064
0107	22		PA		2-6	22-31-51	D08313P		7		GD00800	DC..	1A		YC065-YR328
0108	22		PA		7-0	22-31-51	D08313P		8		SP03101			S	YC051-YC064
0108	22		PA		7-3	22-31-51	D08313P		8		SP03101			S	YC065-YR328
0111	22		PA		1-1	22-11-14	SM00001			S	D08313P		11		YC051-YC052
0111	22		PA		1-2	22-11-14	SM00001			S	D08313P		11		YC053-YC064
0111	22		PA		0-7	22-11-14	SM00001			S	D08313P		11		YC065-YR328
0112	22		PA		1-1	22-11-14	SM00003			S	D08313P		12		YC051-YC052
0112	22		PA		1-2	22-11-14	SM00003			S	D08313P		12		YC053-YC064
0112	22		PA		0-7	22-11-14	SM00003			S	D08313P		12		YC065-YR328
2001B	22		PB	AA	19-11	22-11-11	D00385		1		D04075P	A02			YC051-YC064
2001B	22		PB	AA	19-10	22-11-11	D00385		1		D04075P	A02			YC065-YR328
2001R	22		PB	AA	0-0	22-11-11	D00385		4		D04075P	A01			ALL
2002B	22		PB	AB	19-11	22-12-31	D04075P		B06		D00385		3		YC051-YC064
2002B	22		PB	AB	19-10	22-12-31	D04075P		B06		D00385		3		YC065-YR328
2002R	22		PB	AB	0-0	22-12-31	D04075P		B05		D00385		2		ALL
2027B	22		PB	CB	9-6	22-11-11	D04075P		B08		D00383		4		ALL
2027R	22		PB	CB	0-0	22-11-11	D04075P		B07		D00383		1		ALL
2029B	22		PB	CD	9-6	22-12-31	D04075P		B10		D00383		3		ALL
2029R	22		PB	CD	0-0	22-12-31	D04075P		B09		D00383		2		ALL
2031B	22		X2	CE	11-11	22-11-31	D04075P		B12		D00397		3		ALL
2031R	22		X2	CE	0-0	22-11-31	D04075P		B11		D00397		2		ALL

WIRE LIST

D280A108

91-21-11

Section W5360

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5369	286A5369			AUTOPILOT E1-1 TO ELEX PANEL AND TB803 - SYSTEM A (continued)											
2031Z				CE	0-0	22-11-31	D04075P	PERG	1F		D00397		DED		ALL
2033B	22	PB	CG		11-11	22-11-11	D04075P		B14		D00397		1		ALL
2033R	22	PB	CG		0-0	22-11-11	D04075P		B13		D00397		4		ALL
2176B	22	PB	FF		18-4	31-31-14	D04075P		B17		D10553		1		YC051-YC064
2176B	22	PB	FF		17-11	31-31-14	D04075P		B17		D10553		1		YC065-YR328
2176R	22	PB	FF		0-0	31-31-14	D04075P		B16		D10553		5		ALL
2177B	22	PB	FG		21-5	31-31-14	D04075P		A18		D10551		1		YC051-YC064
2177B	22	PB	FG		21-4	31-31-14	D04075P		A18		D10551		1		YC065-YR328
2177R	22	PB	FG		0-0	31-31-14	D04075P		A17		D10551		5		ALL
3026B	22	PC	CF		21-5	31-31-14	D04075P		A08		D10551		2		YC051-YC064
3026B	22	PC	CF		21-4	31-31-14	D04075P		A08		D10551		2		YC065-YR328
3026R	22	PC	CF		0-0	31-31-14	D04075P		A07		D10551		3		ALL
3026Y	22	PC	CF		0-0	31-31-14	D04075P		A09		D10551		4		ALL
3027B	22	PC	CH		18-4	31-31-14	D04075P		B19		D10553		2		YC051-YC064
3027B	22	PC	CH		17-11	31-31-14	D04075P		B19		D10553		2		YC065-YR328
3027R	22	PC	CH		0-0	31-31-14	D04075P		B18		D10553		3		ALL
3027Y	22	PC	CH		0-0	31-31-14	D04075P		B20		D10553		4		ALL

WIRE LIST

D280A108

91-21-11

Section W5360

Page 9 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W5375	286A5375				AUTOPILOT E1-4 TO ACCEC/PCU - SYSTEM B												
0002	20		PA		8-5	22-11-31	D01691			2		GD00330	DC..	E	*1	YC051-YC055	
0002	20		PA		8-1	22-11-31	D01691			2		GD00330	DC..	E	*1	YC056-YD152	
0002	20		PA		8-10	22-11-31	D01691			2		GD00330	DC..	E	*1	YD153-YN236, YN501-YR328	
0006	22		PA		0-7	22-11-31	D01691			6		D01691		7		YC051-YN236, YN501-YR328	
0007	20		CQ		23-5	47-30-11	D42053P		A05			D04077J		25		YD160-YN236, YN501-YR328	
0008	20		CQ		23-5	47-30-11	D42053P		A06			D04077J		26		YD160-YN236, YN501-YR328	
0009	20		PA		23-5	47-30-11	D42053P		B10			D04077J		27		YD160-YN236, YN501-YR328	
0010	20		PA		23-5	47-30-11	D42053P		A09			D04077J		28		YD160-YN236, YN501-YR328	
0011	20		PA		23-5	SPARE	D42053P		A10			D04077J		29		YD160-YN236, YN501-YR328	
0020	20		CQ		69-11	22-11-12	D04077J		20			D01859		2		YC051-YC053	
0020	20		CQ		69-8	22-11-12	D04077J		20			D01859		2		YC054-YD152	
0020	20		CQ		70-4	22-11-12	D04077J		20			D01859		2		YD153-YL999, YR301-YR328	
0020	20		CQ		60-4	22-11-12	D04077J		20			D01859		2		YN231-YN236, YN501	
0021	20		CQ		69-11	22-11-12	D04077J		21			D01859		1		YC051-YC053	
0021	20		CQ		69-8	22-11-12	D04077J		21			D01859		1		YC054-YD152	
0021	20		CQ		70-4	22-11-12	D04077J		21			D01859		1		YD153-YL999, YR301-YR328	
0021	20		CQ		60-4	22-11-12	D04077J		21			D01859		1		YN231-YN236, YN501	
0022	20		PA		8-5	22-11-31	D01691		22			GD00330	DC..	E	*1	YC051-YC055	
0022	20		PA		8-1	22-11-31	D01691		22			GD00330	DC..	E	*1	YC056-YD152	
0022	20		PA		8-10	22-11-31	D01691		22			GD00330	DC..	E	*1	YD153-YN236, YN501-YR328	
2001B	22		PB	AA	72-8	22-11-31	D04077J		5			D42100J		4		YC051-YD152	
2001B	22		PB	AA	72-9	22-11-31	D04077J		5			D42100J		4		YD153-YL999, YR301-YR328	
2001B	22		PB	AA	62-9	22-11-31	D04077J		5			D42100J		4		YN231-YN236, YN501	
2001R	22		PB	AA	0-0	22-11-31	D04077J		4			D42100J		3		YC051-YN236, YN501-YR328	
2002B	22		PB	AB	66-7	22-11-31	D04077J		7			D43102J		2		YC051-YD152	
2002B	22		PB	AB	66-8	22-11-31	D04077J		7			D43102J		2		YD153-YL999, YR301-YR328	

WIRE LIST

D280A108

91-21-11

Section W5370

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W5375	286A5375			AUTOPILOT E1-4 TO ACCEC/PCU - SYSTEM B (continued)										
2002B	22	PB	AB	56-4	22-11-31	D04077J	7			D43102J	2			YN231-YN236, YN501
2002R	22	PB	AB	0-0	22-11-31	D04077J	6			D43102J	1			YC051-YN236, YN501-YR328
2003B	22	PB	AC	70-4	22-11-31	D04077J	15			SM00003	9			YC051-YC055
2003B	22	PB	AC	70-3	22-11-31	D04077J	15			SM00003	9			YC056-YD152
2003B	22	PB	AC	70-11	22-11-31	D04077J	15			SM00003	9			YD153-YL999, YR301-YR328
2003B	22	PB	AC	61-0	22-11-31	D04077J	15			SM00003	9			YN231-YN236, YN501
2003R	22	PB	AC	0-0	22-11-31	D04077J	14			SM00001	9			YC051-YN236, YN501-YR328
2004B	22	PB	AD	6-0	22-11-31	D01707	1			SM00003	9			YC051-YC055
2004B	22	PB	AD	6-2	22-11-31	D01707	1			SM00003	9			YC056-YD152
2004B	22	PB	AD	6-4	22-11-31	D01707	1			SM00003	9			YD153-YN236, YN501-YR328
2004R	22	PB	AD	0-0	22-11-31	D01707	2			SM00001	9			YC051-YN236, YN501-YR328
2005B	22	PB	AE	1-0	22-11-31	D01691	10			SM00003	9			YC051-YD152
2005B	22	PB	AE	1-1	22-11-31	D01691	10			SM00003	9			YD153-YN236, YN501-YR328
2005R	22	PB	AE	0-0	22-11-31	D01691	9			SM00001	9			YC051-YN236, YN501-YR328
2006B	22	PB	AF	70-10	22-11-31	D04077J	38			D01691	8			YC051-YC055
2006B	22	PB	AF	70-9	22-11-31	D04077J	38			D01691	8			YC056-YD152
2006B	22	PB	AF	71-5	22-11-31	D04077J	38			D01691	8			YD153-YL999, YR301-YR328
2006B	22	PB	AF	61-6	22-11-31	D04077J	38			D01691	8			YN231-YN236, YN501
2006R	22	PB	AF	0-0	22-11-31	D04077J	37			D01691	5			YC051-YN236, YN501-YR328
2007B	20	PB	AG	70-10	22-11-31	D04077J	17			D01691	1			YC051-YC055
2007B	20	PB	AG	70-9	22-11-31	D04077J	17			D01691	1			YC056-YD152
2007B	20	PB	AG	71-5	22-11-31	D04077J	17			D01691	1			YD153-YL999, YR301-YR328
2007B	20	PB	AG	61-6	22-11-31	D04077J	17			D01691	1			YN231-YN236, YN501
2007R	20	PB	AG	0-0	22-11-31	D04077J	16			D01691	21			YC051-YN236, YN501-YR328
2008B	22	X2	AH	66-7	22-11-11	D04077J	19			D43102J	4			YC051-YD152
2008B	22	X2	AH	66-8	22-11-11	D04077J	19			D43102J	4			YD153-YL999, YR301-YR328
2008B	22	X2	AH	56-4	22-11-11	D04077J	19			D43102J	4			YN231-YN236, YN501

WIRE LIST

D280A108

91-21-11

Section W5370

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5375	286A5375			AUTOPILOT E1-4 TO ACCEC/PCU - SYSTEM B (continued)											
2008R	22	X2		AH	0-0	22-11-11	D04077J	18			D43102J	3			YC051-YN236, YN501-YR328
2008Z				AH	0-0	22-11-11	D04077J	S/R			D43102J	S/R			YC051-YN236, YN501-YR328
2010B	22	PB	AJ		59-8	27-18-11	D42100J	2			D42053P	A02			YC051-YC055
2010B	22	PB	AJ		59-9	27-18-11	D42100J	2			D42053P	A02			YC056-YL999, YR301-YR328
2010B	22	PB	AJ		49-3	27-18-11	D42100J	2			D42053P	A02			YN231-YN236, YN501
2010R	22	PB	AJ		0-0	27-18-11	D42100J	1			D42053P	A01			YC051-YN236, YN501-YR328
2011B	22	PB	AK		59-8	27-62-14	D42100J	12			D42053P	A04			YC051-YC055
2011B	22	PB	AK		59-9	27-62-14	D42100J	12			D42053P	A04			YC056-YL999, YR301-YR328
2011B	22	PB	AK		49-3	27-62-14	D42100J	12			D42053P	A04			YN231-YN236, YN501
2011R	22	PB	AK		0-0	27-62-14	D42100J	11			D42053P	A03			YC051-YN236, YN501-YR328
2012B	22	X2	AL		59-8	27-32-21	D42100J	21			D42053P	A08			YC051-YC055
2012B	22	X2	AL		59-9	27-32-21	D42100J	21			D42053P	A08			YC056-YL999, YR301-YR328
2012B	22	X2	AL		49-3	27-32-21	D42100J	21			D42053P	A08			YN231-YN236, YN501
2012R	22	X2	AL		0-0	27-32-21	D42100J	20			D42053P	A07			YC051-YN236, YN501-YR328
2012Z				AL	0-0	27-32-21	D42100J	S/R			D42053P	PERG	1F		YC051-YN236, YN501-YR328
2013B	20	X2	OM		72-8	27-62-11	D42100J	30			D43908P	2			YL953-YL999, YR301-YR328
2013R	20	X2	OM		0-0	27-62-11	D42100J	29			D43908P	1			YL953-YL999, YR301-YR328
2013Z				OM	0-0	27-62-11	D42100J	S/R			D43908P	PERS	1A		YL953-YL999, YR301-YR328
2014B	20	X2	ON		72-8	27-62-11	D42100J	32			D43908P	4			YL953-YL999, YR301-YR328
2014R	20	X2	ON		0-0	27-62-11	D42100J	31			D43908P	3			YL953-YL999, YR301-YR328
2014Z				ON	0-0	27-62-11	D42100J	S/R			D43908P	PERS	1A		YL953-YL999, YR301-YR328
2015B	20	X2	OP		72-8	27-62-11	D42100J	34			D43908P	6			YL953-YL999, YR301-YR328

WIRE LIST
D280A108

91-21-11
Section W5370
Page 3
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5375	286A5375				AUTOPILOT E1-4 TO ACCEC/PCU - SYSTEM B (continued)										
2015R	20	X2	OP		0-0	27-62-11	D42100J	33			D43908P	5			YL953-YL999, YR301-YR328
2015Z			OP		0-0	27-62-11	D42100J	S/R			D43908P	PERS	1A		YL953-YL999, YR301-YR328
2016B	20	X2	OQ		72-8	27-62-11	D42100J	36			D43908P	8			YL953-YL999, YR301-YR328
2016R	20	X2	OQ		0-0	27-62-11	D42100J	35			D43908P	7			YL953-YL999, YR301-YR328
2016Z			OQ		0-0	27-62-11	D42100J	S/R			D43908P	PERS	1A		YL953-YL999, YR301-YR328
3001B	22	PC	CA		72-8	22-11-31	D04077J	2			D42100J	9			YC051-YD152
3001B	22	PC	CA		72-9	22-11-31	D04077J	2			D42100J	9			YD153-YL999, YR301-YR314
3001B	22	PC	CA		62-9	22-11-31	D04077J	2			D42100J	9			YN231-YN236, YN501
3001B	22	PB	CA		72-9	22-11-31	D04077J	2			D42100J	9			YR315-YR328
3001R	22	PC	CA		0-0	22-11-31	D04077J	1			D42100J	8			YC051-YN236, YN501-YR314
3001R	22	PB	CA		0-0	22-11-31	D04077J	1			D42100J	8			YR315-YR328
3001Y	22	PC	CA		0-0	22-11-31	D04077J	3			D42100J	10			YC051-YN236, YN501-YR314
3002B	22	PC	CB		66-7	22-11-31	D04077J	9			D43102J	6			YC051-YD152
3002B	22	PC	CB		66-8	22-11-31	D04077J	9			D43102J	6			YD153-YL999, YR301-YR314
3002B	22	PC	CB		56-4	22-11-31	D04077J	9			D43102J	6			YN231-YN236, YN501
3002B	22	PB	CB		66-8	22-11-31	D04077J	9			D43102J	6			YR315-YR328
3002R	22	PC	CB		0-0	22-11-31	D04077J	8			D43102J	5			YC051-YN236, YN501-YR314
3002R	22	PB	CB		0-0	22-11-31	D04077J	8			D43102J	5			YR315-YR328
3002Y	22	PC	CB		0-0	22-11-31	D04077J	10			D43102J	7			YC051-YN236, YN501-YR314
3003B	22	PC	CC		70-7	22-11-31	D04077J	12			D01707	5			YC051-YC055
3003B	22	PC	CC		70-9	22-11-31	D04077J	12			D01707	5			YC056-YD152
3003B	22	PC	CC		70-0	22-11-31	D04077J	12			D01707	5			YD153-YL999, YR301-YR328
3003B	22	PC	CC		60-0	22-11-31	D04077J	12			D01707	5			YN231-YN236, YN501
3003R	22	PC	CC		0-0	22-11-31	D04077J	11			D01707	4			YC051-YN236, YN501-YR328
3003Y	22	PC	CC		0-0	22-11-31	D04077J	13			D01707	3			YC051-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W5370

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5375	286A5375				AUTOPILOT E1-4 TO ACCEC/PCU - SYSTEM B (continued)										
3004B	22	PC	CD		70-10	22-11-31	D04077J		33		D01691	12			YC051-YC055
3004B	22	PC	CD		70-9	22-11-31	D04077J		33		D01691	12			YC056-YD152
3004B	22	PC	CD		71-5	22-11-31	D04077J		33		D01691	12			YD153-YL999, YR301-YR328
3004B	22	PC	CD		61-6	22-11-31	D04077J		33		D01691	12			YN231-YN236, YN501
3004R	22	PC	CD		0-0	22-11-31	D04077J		32		D01691	11			YC051-YN236, YN501-YR328
3004Y	22	PC	CD		0-0	22-11-31	D04077J		34		D01691	13			YC051-YN236, YN501-YR328
3005B	22	X3	CE		66-7	22-12-41	D04077J		23		D43102J	9			YC051-YD152
3005B	22	X3	CE		66-8	22-12-41	D04077J		23		D43102J	9			YD153-YL999, YR301-YR328
3005B	22	X3	CE		56-4	22-12-41	D04077J		23		D43102J	9			YN231-YN236, YN501
3005R	22	X3	CE		0-0	22-12-41	D04077J		22		D43102J	8			YC051-YN236, YN501-YR328
3005Y	22	X3	CE		0-0	22-12-41	D04077J		24		D43102J	10			YC051-YN236, YN501-YR328
3005Z			CE		0-0	22-12-41	D04077J		S/R		D43102J	S/R			YC051-YN236, YN501-YR328
3011B	22	PC	CG		59-8	27-62-14	D42100J		17		D42053P	B05			YC051-YC055
3011B	22	PC	CG		59-9	27-62-14	D42100J		17		D42053P	B05			YC056-YL999, YR301-YR328
3011B	22	PC	CG		49-3	27-62-14	D42100J		17		D42053P	B05			YN231-YN236, YN501
3011R	22	PC	CG		0-0	27-62-14	D42100J		16		D42053P	B04			YC051-YN236, YN501-YR328
3011Y	22	PC	CG		0-0	27-62-14	D42100J		18		D42053P	B06			YC051-YN236, YN501-YR328
3012B	22	X3	CH		59-8	27-32-21	D42100J		25		D42053P	B08			YC051-YC055
3012B	22	X3	CH		59-9	27-32-21	D42100J		25		D42053P	B08			YC056-YL999, YR301-YR328
3012B	22	X3	CH		49-3	27-32-21	D42100J		25		D42053P	B08			YN231-YN236, YN501
3012R	22	X3	CH		0-0	27-32-21	D42100J		24		D42053P	B07			YC051-YN236, YN501-YR328
3012Y	22	X3	CH		0-0	27-32-21	D42100J		26		D42053P	B09			YC051-YN236, YN501-YR328
3012Z			CH		0-0	27-32-21	D42100J		S/R		D42053P	PERG	1F		YC051-YN236, YN501-YR328
3015B	22	PC	CM		59-8	27-18-11	D42100J		6		D42053P	B02			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5370

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5375	286A5375			AUTOPILOT E1-4 TO ACCEC/PCU - SYSTEM B (continued)											
3015B	22	PC	CM		59-9	27-18-11	D42100J		6		D42053P	B02			YC056-YL999, YR301-YR328
3015B	22	PC	CM		49-3	27-18-11	D42100J		6		D42053P	B02			YN231-YN236, YN501
3015R	22	PC	CM		0-0	27-18-11	D42100J		5		D42053P	B01			YC051-YN236, YN501-YR328
3015Y	22	PC	CM		0-0	27-18-11	D42100J		7		D42053P	B03			YC051-YN236, YN501-YR328
YAAA					0-0	22-11-31	GD01505	ST..	E		GD00947	ST..	E		YC054-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W5370

Page 6 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description		From				To					
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5381	286A5381			AUTOPILOT E1-1 TO AB1050L											
2001B	22	VG	AA		121-11	22-11-81	D45551P	B01			D45501P	2			YC064
2001B	22	VG	AA		122-0	22-11-81	D45551P	B01			D45501J	2			YC065-YC070
2001B	22	VG	AA		122-0	22-11-81	D45551P	B01			D45501J	15			YD151-YD155
2001B	22	VG	AA		118-6	22-11-81	D45551P	B01			D45501J	15			YD157-YL999, YR301-YR328
2001B	22	VG	AA		99-2	22-11-81	D45551P	B01			D45501J	15			YN231-YN501
2001R	22	VG	AA		0-0	22-11-81	D45551P	A01			D45501P	1			YC064
2001R	22	VG	AA		0-0	22-11-81	D45551P	A01			D45501J	1			YC065-YC070
2001R	22	VG	AA		0-0	22-11-81	D45551P	A01			D45501J	14			YD151-YR328
2001Z			AA		0-0	22-11-81	D45551P	PERG	1F		D45501P	S/R			YC064
2001Z			AA		0-0	22-11-81	D45551P	PERG	1F		D45501J	S/R			YC065-YR328
2002B	18	HF	AB		121-11	22-11-81	D45551P	G			D45501P	4	18		YC064
2002B	18	HF	AB		122-0	22-11-81	D45551P	G			D45501J	4	18		YC065-YC070
2002B	18	HF	AB		122-0	22-11-81	D45551P	K			D45501J	3	18		YD151-YD155
2002B	18	HF	AB		118-6	22-11-81	D45551P	K			D45501J	3	18		YD157-YL999, YR301-YR328
2002B	18	HF	AB		99-2	22-11-81	D45551P	K			D45501J	3	18		YN231-YN501
2002R	18	HF	AB		0-0	22-11-81	D45551P	F			D45501P	3	18		YC064
2002R	18	HF	AB		0-0	22-11-81	D45551P	F			D45501J	3	18		YC065-YC070
2002R	18	HF	AB		0-0	22-11-81	D45551P	J			D45501J	1	18		YD151-YR328
2002Z			AB		0-0	22-11-81	D45551P	PERG	1F		D45501P	S/R			YC064
2002Z			AB		0-0	22-11-81	D45551P	PERG	1F		D45501J	S/R			YC065-YR328
2003B	22	VG	AC		121-11	22-11-81	D45551P	B03			D45501P	6			YC064
2003B	22	VG	AC		122-0	22-11-81	D45551P	B03			D45501J	6			YC065-YC070
2003B	22	VG	AC		122-0	22-11-81	D45551P	B03			D45501J	17			YD151-YD155
2003B	22	VG	AC		118-6	22-11-81	D45551P	B03			D45501J	17			YD157-YL999, YR301-YR328
2003B	22	VG	AC		99-2	22-11-81	D45551P	B03			D45501J	17			YN231-YN501
2003R	22	VG	AC		0-0	22-11-81	D45551P	A03			D45501P	5			YC064
2003R	22	VG	AC		0-0	22-11-81	D45551P	A03			D45501J	5			YC065-YC070
2003R	22	VG	AC		0-0	22-11-81	D45551P	A03			D45501J	16			YD151-YR328
2003Z			AC		0-0	22-11-81	D45551P	PERG	1F		D45501P	S/R			YC064
2003Z			AC		0-0	22-11-81	D45551P	PERG	1F		D45501J	S/R			YC065-YR328
2004B	22	VG	AD		121-11	22-11-81	D45551P	B04			D45501P	8			YC064
2004B	22	VG	AD		122-0	22-11-81	D45551P	B04			D45501J	8			YC065-YC070
2004B	22	VG	AD		122-0	22-11-81	D45551P	B10			D45501J	19			YD151-YD155
2004B	22	VG	AD		118-6	22-11-81	D45551P	B10			D45501J	19			YD157-YL999, YR301-YR328
2004B	22	VG	AD		99-2	22-11-81	D45551P	B10			D45501J	19			YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W5380

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W5381	286A5381	AUTOPILOT E1-1 TO AB1050L (continued)													
2004R	22	VG	AD	0-0	22-11-81	D45551P	A04		D45501P	7				YC064	
2004R	22	VG	AD	0-0	22-11-81	D45551P	A04		D45501J	7				YC065-YC070	
2004R	22	VG	AD	0-0	22-11-81	D45551P	A10		D45501J	18				YD151-YR328	
2004Z			AD	0-0	22-11-81	D45551P	PERG	1F	D45501P	S/R				YC064	
2004Z			AD	0-0	22-11-81	D45551P	PERG	1F	D45501J	S/R				YC065-YR328	
2005B	22	VG	AE	121-11	22-11-81	D45551P	B05		D45501P	10				YC064	
2005B	22	VG	AE	122-0	22-11-81	D45551P	B05		D45501J	10				YC065-YC070	
2005B	22	VG	AE	122-0	22-11-81	D45551P	B06		D45501J	21				YD151-YD155	
2005B	22	VG	AE	118-6	22-11-81	D45551P	B06		D45501J	21				YD157-YL999, YR301-YR328	
2005B	22	VG	AE	99-2	22-11-81	D45551P	B06		D45501J	21				YN231-YN501	
2005R	22	VG	AE	0-0	22-11-81	D45551P	A05		D45501P	9				YC064	
2005R	22	VG	AE	0-0	22-11-81	D45551P	A05		D45501J	9				YC065-YC070	
2005R	22	VG	AE	0-0	22-11-81	D45551P	A06		D45501J	9				YD151-YR328	
2005Z			AE	0-0	22-11-81	D45551P	PERG	1F	D45501P	S/R				YC064	
2005Z			AE	0-0	22-11-81	D45551P	PERG	1F	D45501J	S/R				YC065-YR328	
2008B	22	VG	AH	121-11	SPARE	D45551P	B02		D45501P	15				YC064	
2008B	22	VG	AH	122-0	SPARE	D45551P	B02		D45501J	15				YC065-YC070	
2008B	22	VG	AH	122-0	SPARE	D45551P	B02		D45501J	13				YD151-YD155	
2008B	22	VG	AH	118-6	SPARE	D45551P	B02		D45501J	13				YD157-YL999, YR301-YR328	
2008B	22	VG	AH	99-2	SPARE	D45551P	B02		D45501J	13				YN231-YN501	
2008R	22	VG	AH	0-0	SPARE	D45551P	A02		D45501P	14				YC064	
2008R	22	VG	AH	0-0	SPARE	D45551P	A02		D45501J	14				YC065-YC070	
2008R	22	VG	AH	0-0	SPARE	D45551P	A02		D45501J	4				YD151-YR328	
2008Z			AH	0-0	SPARE	D45551P	PERG	1F	D45501P	S/R				YC064	
2008Z			AH	0-0	SPARE	D45551P	PERG	1F	D45501J	S/R				YC065-YR328	
2009B	20	HF	AI	121-11	SPARE	D45551P	B08		D45501P	17				YC064	
2009B	20	HF	AI	122-0	SPARE	D45551P	B08		D45501J	17				YC065-YC070	
2009B	20	HF	AI	122-0	SPARE	D45551P	B09		D45501J	10				YD151-YD155	
2009B	20	HF	AI	118-6	SPARE	D45551P	B09		D45501J	10				YD157-YL999, YR301-YR328	
2009B	20	HF	AI	99-2	SPARE	D45551P	B09		D45501J	10				YN231-YN501	
2009R	20	HF	AI	0-0	SPARE	D45551P	A08		D45501P	16				YC064	
2009R	20	HF	AI	0-0	SPARE	D45551P	A08		D45501J	16				YC065-YC070	
2009R	20	HF	AI	0-0	SPARE	D45551P	A09		D45501J	2				YD151-YR328	
2009Z			AI	0-0	SPARE	D45551P	PERG	1F	D45501P	S/R				YC064	
2009Z			AI	0-0	SPARE	D45551P	PERG	1F	D45501J	S/R				YC065-YR328	
3001B	22	HG	CA	121-11	22-11-81	D45551P	B06		D45501P	12				YC064	

WIRE LIST

D280A108

91-21-11

Section W5380

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5381	286A5381				AUTOPILOT E1-1 TO AB1050L (continued)										
3001B	22	HG	CA		122-0	22-11-81	D45551P	B06			D45501J	12			YC065-YC070
3001B	22	HG	CA		122-0	22-11-81	D45551P	B07			D45501J	23			YD151-YD155
3001B	22	HG	CA		118-6	22-11-81	D45551P	B07			D45501J	23			YD157-YL999, YR301-YR328
3001B	22	HG	CA		99-2	22-11-81	D45551P	B07			D45501J	23			YN231-YN501
3001R	22	HG	CA		0-0	22-11-81	D45551P	A06			D45501P	11			YC064
3001R	22	HG	CA		0-0	22-11-81	D45551P	A06			D45501J	11			YC065-YC070
3001R	22	HG	CA		0-0	22-11-81	D45551P	A07			D45501J	22			YD151-YR328
3001Y	22	HG	CA		0-0	22-11-81	D45551P	A07			D45501P	13			YC064
3001Y	22	HG	CA		0-0	22-11-81	D45551P	A07			D45501J	13			YC065-YC070
3001Y	22	HG	CA		0-0	22-11-81	D45551P	A08			D45501J	24			YD151-YR328
3001Z			CA		0-0	22-11-81	D45551P	PERG	1F		D45501P	S/R			YC064
3001Z			CA		0-0	22-11-81	D45551P	PERG	1F		D45501J	S/R			YC065-YR328
W5383	286A5383				AUTOPILOT E1-4 TO AB1050R										
2001B	22	VG	AA		120-4	22-11-81	D45553J		2		D45503P	2			YC064
2001B	22	VG	AA		120-3	22-11-81	D45553J		2		D45503J	2			YC065-YC070
2001B	22	VG	AA		120-3	22-11-81	D45553J		19		D45503J	19			YD151-YL999, YR301-YR328
2001B	22	VG	AA		100-11	22-11-81	D45553J		19		D45503J	19			YN231-YN501
2001R	22	VG	AA		0-0	22-11-81	D45553J		1		D45503P	1			YC064
2001R	22	VG	AA		0-0	22-11-81	D45553J		1		D45503J	1			YC065-YC070
2001R	22	VG	AA		0-0	22-11-81	D45553J		18		D45503J	18			YD151-YR328
2001Z			AA		0-0	22-11-81	D45553J	S/R			D45503P	S/R			YC064
2001Z			AA		0-0	22-11-81	D45553J	S/R			D45503J	S/R			YC065-YR328
2002B	22	VG	AB		120-4	22-11-81	D45553J		4		D45503P	4			YC064
2002B	22	VG	AB		120-3	22-11-81	D45553J		4		D45503J	4			YC065-YC070
2002B	22	VG	AB		120-3	22-11-81	D45553J		15		D45503J	15			YD151-YL999, YR301-YR328
2002B	22	VG	AB		100-11	22-11-81	D45553J		15		D45503J	15			YN231-YN501
2002R	22	VG	AB		0-0	22-11-81	D45553J		3		D45503P	3			YC064
2002R	22	VG	AB		0-0	22-11-81	D45553J		3		D45503J	3			YC065-YC070
2002R	22	VG	AB		0-0	22-11-81	D45553J		14		D45503J	14			YD151-YR328
2002Z			AB		0-0	22-11-81	D45553J	S/R			D45503P	S/R			YC064
2002Z			AB		0-0	22-11-81	D45553J	S/R			D45503J	S/R			YC065-YR328
2003B	18	HF	AC		120-4	22-11-81	D45553J		6	18	D45503P	6	18		YC064
2003B	18	HF	AC		120-3	22-11-81	D45553J		6	18	D45503J	6	18		YC065-YC070
2003B	18	HF	AC		120-3	22-11-81	D45553J		3	18	D45503J	3	18		YD151-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W5380

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5383		286A5383			AUTOPILOT E1-4 TO AB1050R (continued)											
2003B		18		HF	AC	100-11	22-11-81	D45553J	3	18		D45503J	3	18		YN231-YN501
2003R		18		HF	AC	0-0	22-11-81	D45553J	5	18		D45503P	5	18		YC064
2003R		18		HF	AC	0-0	22-11-81	D45553J	5	18		D45503J	5	18		YC065-YC070
2003R		18		HF	AC	0-0	22-11-81	D45553J	1	18		D45503J	1	18		YD151-YR328
2003Z					AC	0-0	22-11-81	D45553J	S/R			D45503P	S/R			YC064
2003Z					AC	0-0	22-11-81	D45553J	S/R			D45503J	S/R			YC065-YR328
2004B		22		VG	AD	120-4	22-11-81	D45553J	8			D45503P	8			YC064
2004B		22		VG	AD	120-3	22-11-81	D45553J	8			D45503J	8			YC065-YC070
2004B		22		VG	AD	120-3	22-11-81	D45553J	17			D45503J	17			YD151-YL999, YR301-YR328
2004B		22		VG	AD	100-11	22-11-81	D45553J	17			D45503J	17			YN231-YN501
2004R		22		VG	AD	0-0	22-11-81	D45553J	7			D45503P	7			YC064
2004R		22		VG	AD	0-0	22-11-81	D45553J	7			D45503J	7			YC065-YC070
2004R		22		VG	AD	0-0	22-11-81	D45553J	16			D45503J	16			YD151-YR328
2004Z					AD	0-0	22-11-81	D45553J	S/R			D45503P	S/R			YC064
2004Z					AD	0-0	22-11-81	D45553J	S/R			D45503J	S/R			YC065-YR328
2005B		22		VG	AE	120-4	22-11-81	D45553J	10			D45503P	10			YC064
2005B		22		VG	AE	120-3	22-11-81	D45553J	10			D45503J	10			YC065-YC070
2005B		22		VG	AE	120-3	22-11-81	D45553J	21			D45503J	21			YD151-YL999, YR301-YR328
2005B		22		VG	AE	100-11	22-11-81	D45553J	21			D45503J	21			YN231-YN501
2005R		22		VG	AE	0-0	22-11-81	D45553J	9			D45503P	9			YC064
2005R		22		VG	AE	0-0	22-11-81	D45553J	9			D45503J	9			YC065-YR328
2005Z					AE	0-0	22-11-81	D45553J	S/R			D45503P	S/R			YC064
2005Z					AE	0-0	22-11-81	D45553J	S/R			D45503J	S/R			YC065-YR328
2008B		22		VG	AH	120-4	SPARE	D45553J	15			D45503P	15			YC064
2008B		22		VG	AH	120-3	SPARE	D45553J	15			D45503J	15			YC065-YC070
2008B		22		VG	AH	120-3	SPARE	D45553J	13			D45503J	13			YD151-YL999, YR301-YR328
2008B		22		VG	AH	100-11	SPARE	D45553J	13			D45503J	13			YN231-YN501
2008R		22		VG	AH	0-0	SPARE	D45553J	14			D45503P	14			YC064
2008R		22		VG	AH	0-0	SPARE	D45553J	14			D45503J	14			YC065-YC070
2008R		22		VG	AH	0-0	SPARE	D45553J	4			D45503J	4			YD151-YR328
2008Z					AH	0-0	SPARE	D45553J	S/R			D45503P	S/R			YC064
2008Z					AH	0-0	SPARE	D45553J	S/R			D45503J	S/R			YC065-YR328
2009B		20		HF	AI	120-4	SPARE	D45553J	17			D45503P	17			YC064
2009B		20		HF	AI	120-3	SPARE	D45553J	17			D45503J	17			YC065-YC070
2009B		20		HF	AI	120-3	SPARE	D45553J	10			D45503J	10			YD151-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W5380

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5383	286A5383			AUTOPILOT E1-4 TO AB1050R (continued)											
2009B	20	HF	AI		100-11	SPARE	D45553J		10		D45503J		10		YN231-YN501
2009R	20	HF	AI		0-0	SPARE	D45553J		16		D45503P		16		YC064
2009R	20	HF	AI		0-0	SPARE	D45553J		16		D45503J		16		YC065-YC070
2009R	20	HF	AI		0-0	SPARE	D45553J		2		D45503J		2		YD151-YR328
2009Z			AI		0-0	SPARE	D45553J		S/R		D45503P		S/R		YC064
2009Z			AI		0-0	SPARE	D45553J		S/R		D45503J		S/R		YC065-YR328
3001B	22	HG	CA		120-4	22-11-81	D45553J		12		D45503P		12		YC064
3001B	22	HG	CA		120-3	22-11-81	D45553J		12		D45503J		12		YC065-YC070
3001B	22	HG	CA		120-3	22-11-81	D45553J		23		D45503J		23		YD151-YL999, YR301-YR328
3001B	22	HG	CA		100-11	22-11-81	D45553J		23		D45503J		23		YN231-YN501
3001R	22	HG	CA		0-0	22-11-81	D45553J		11		D45503P		11		YC064
3001R	22	HG	CA		0-0	22-11-81	D45553J		11		D45503J		11		YC065-YC070
3001R	22	HG	CA		0-0	22-11-81	D45553J		22		D45503J		22		YD151-YR328
3001Y	22	HG	CA		0-0	22-11-81	D45553J		13		D45503P		13		YC064
3001Y	22	HG	CA		0-0	22-11-81	D45553J		13		D45503J		13		YC065-YC070
3001Y	22	HG	CA		0-0	22-11-81	D45553J		24		D45503J		24		YD151-YR328
3001Z			CA		0-0	22-11-81	D45553J		S/R		D45503P		S/R		YC064
3001Z			CA		0-0	22-11-81	D45553J		S/R		D45503J		S/R		YC065-YR328

WIRE LIST

D280A108

91-21-11

Section W5380

Page 5 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5397	286A5397			AUTOTHROTTLE SERVO MOTOR 2 TO E1-1											
0001	22		PA		1-2	22-31-41	D10027			AA	GD01838	ST..	E		ALL
0002	22		PA		1-1	22-31-41	D10027	10			GD01837	DC..	E		ALL
0003	22		PA		0-7	22-31-41	D10027	11			D10027	1			ALL
0004	22		PA		1-2	22-31-41	D10027			AD	GD01838	ST..	E		ALL
2001B	22		PB	AC	16-7	22-31-41	D10027	3			D41161P	B03			ALL
2001R	22		PB	AC	0-0	22-31-41	D10027	9			D41161P	A03			ALL
2002B	24		PL	AB	16-7	22-31-41	D10027	6			D41161P	B02			ALL
2002R	24		PL	AB	0-0	22-31-41	D10027	14			D41161P	A02			ALL
2501B	24		Y2	AA	16-7	22-31-41	D10027	8			D41161P	B01			ALL
2501R	24		Y2	AA	0-0	22-31-41	D10027	7			D41161P	A01			ALL
2501Z				AA	0-0	22-31-41	D10027			AA	D41161P	PERG	1F		ALL
2504B	24		Y2	AD	16-7	22-31-41	D10027	13			D41161P	B04			ALL
2504R	24		Y2	AD	0-0	22-31-41	D10027	12			D41161P	A04			ALL
2504Z				AD	0-0	22-31-41	D10027			AD	D41161P	PERG	1F		ALL

WIRE LIST

D280A108

91-21-11

Section W5390

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W5409	286A5409				DFDAU E3-2 SHELF TO DISCONNECT PANEL OF FLIGHT RECORDER												
0001	22		PA		101-8	31-31-11		D43209P	A06			D43267P	12			YC051-YC055	
0001	22		PA		101-9	31-31-11		D43209P	A06			D43267P	12			YC056-YL999, YR301-YR328	
0001	22		PA		82-3	31-31-11		D43209P	A06			D43267P	12			YN231-YN501	
0002	22		PA		101-8	31-31-11		D43209P	A03			D43267P	13			YC051-YC055	
0002	22		PA		101-9	31-31-11		D43209P	A03			D43267P	13			YC056-YL999, YR301-YR328	
0002	22		PA		82-3	31-31-11		D43209P	A03			D43267P	13			YN231-YN501	
0003	20		PA		3-4	31-31-11		D43267P	11			GD03864	DC..	1		ALL	
0004	20		PA		3-4	31-31-11		D43267P	10			GD03864	DC..	1		ALL	
0005	20		PA		3-4	31-31-11		D43267P	9			GD03864	AC..	1		ALL	
0007	22		PA		101-8	31-31-11		D43209P	A07			D43267P	7			YC051-YC055	
0007	22		PA		101-9	31-31-11		D43209P	A07			D43267P	7			YC056-YL999, YR301-YR328	
0007	22		PA		82-3	31-31-11		D43209P	A07			D43267P	7			YN231-YN501	
0008	22		PA		101-8	31-31-11		D43209P	A08			D43267P	8			YC051-YC055	
0008	22		PA		101-9	31-31-11		D43209P	A08			D43267P	8			YC056-YL999, YR301-YR328	
0008	22		PA		82-3	31-31-11		D43209P	A08			D43267P	8			YN231-YN501	
2001B	22		X2	AA	101-8	31-31-11		D43209P	A02			D43267P	2			YC051-YC055	
2001B	22		X2	AA	101-9	31-31-11		D43209P	A02			D43267P	2			YC056-YL999, YR301-YR328	
2001B	22		X2	AA	82-3	31-31-11		D43209P	A02			D43267P	2			YN231-YN501	
2001R	22		X2	AA	0-0	31-31-11		D43209P	A01			D43267P	1			ALL	
2001Z				AA	0-0	31-31-11		D43209P	PERG	1F		D43267P				ALL	
2002B	22		X2	AB	101-8	31-31-11		D43209P	A05			D43267P	5			YC051-YC055	
2002B	22		X2	AB	101-9	31-31-11		D43209P	A05			D43267P	5			YC056-YL999, YR301-YR328	
2002B	22		X2	AB	82-3	31-31-11		D43209P	A05			D43267P	5			YN231-YN501	
2002R	22		X2	AB	0-0	31-31-11		D43209P	A04			D43267P	4			ALL	
2002Z				AB	0-0	31-31-11		D43209P	PERG	1F		D43267P				ALL	
FRAA					0-0	31-31-11		D43267P			FA	D43267P	6			ALL	
FRAB					0-0	31-31-11		D43267P			FA	D43267P	S/R			ALL	
FRAC					0-0	31-31-11		D43267P			FC	D43267P	3			ALL	
FRAD					0-0	31-31-11		D43267P			FC	D43267P	S/R			ALL	

WIRE LIST

D280A108

91-21-11

Section W5400

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I	W5411	286A5411					VHF-2 ANTENNA-E/E TO STA 506 BOTTOM								
	001CO			AA	0-0	23-12-11	D04133P		= C1		D04137J		= C1		YC051-YC060
I	001CO			AA	0-0	23-12-21	D04131J		= C1		D04137J		= C1		YC061-YR328
	001CX		0G	AA	18-2	23-12-11	D04133P		= A1		D04137J		= A1		YC051-YC060
I	001CX		0G	AA	16-8	23-12-21	D04131J		= A1		D04137J		= A1		YC061-YR328
I	W5413	286A5413					VHF-1 ANTENNA-E/E TO STA 630.36								
	001CO			AA	0-0	23-12-21	D00115		= C1		D04131J		= C1		YC051-YC060
	001CO			AA	0-0	23-12-11	D00115		= C1		D04141J		= C1		YC061-YC063
I	001CO			AA	0-0	23-12-11	D00115		= C1		D04133P		= C1		YC064-YL999, YR301-YR328
	001CO			AA	0-0	23-12-11	D04133P		= C1		D00115		= C1		YN231-YN501
	001CX		0G	AA	70-2	23-12-21	D00115		= A1		D04131J		= A1		YC051-YC060
	001CX		0G	AA	69-2	23-12-11	D00115		= A1		D04141J		= A1		YC061-YC063
I	001CX		0G	AA	71-7	23-12-11	D00115		= A1		D04133P		= A1		YC064-YL999, YR301-YR328
	001CX		0G	AA	61-7	23-12-11	D04133P		= A1		D00115		= A1		YN231-YN501
I	W5415	286A5415					VHF-3 ANTENNA-E/E TO STA 470.88 BOTTOM								
I	001CO			AA	0-0	23-12-31	D43301P		= C1		D00335		= C1		ALL
	001CX		0G	AA	21-6	23-12-31	D43301P		= A1		D00335		= A1		YC051-YC055
I	001CX		0G	AA	21-8	23-12-31	D43301P		= A1		D00335		= A1		YC056-YR328
I	W5417	286A5417					VHF-2 ANTENNA BOTTOM								
	001CO			AA	0-0	23-12-11	D04137P		= C1		D00117		= C1		YC051-YC060
I	001CO			AA	0-0	23-12-21	D04137P		= C1		D00117		= C1		YC061-YR328
	001CX		0G	AA	71-9	23-12-11	D04137P		= A1		D00117		= A1		YC051-YC060
I	001CX		0G	AA	71-9	23-12-21	D04137P		= A1		D00117		= A1		YC061-YL999, YR301-YR328
	001CX		0G	AA	61-7	23-12-21	D04137P		= A1		D00117		= A1		YN231-YN501
	W5419	286A5419					VHF-1 ANTENNA (TOP) E1-3 TO E1-5 BRACKET								
	001CO			AA	0-0	23-12-11	D04133P		= C1		D04141P		= C1		YC061-YC063
	001CX		0G	AA	2-3	23-12-11	D04133P		= A1		D04141P		= A1		YC061-YC063

WIRE LIST

D280A108

91-21-11

Section W5410

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5431	286A5431				-800 VOICE RECORDER (WITH E6)										
0001	20		PA		4-1	23-71-01	D00177		3		GD00431	AC..	1		YC051-YL963, YN236-YN501
0001	20		PA		4-3	23-71-01	D00177		3		GD00431	AC..	1		YL964-YL999, YR301-YR328
0001	20		PA		3-11	23-71-01	D00177		3		GD00431	AC..	1		YN231-YN235
0002	20		PA		105-5	23-71-01	D00177		2		D04371P	A01			YC051-YC055
0002	20		PA		106-8	23-71-01	D00177		2		D04371P	A01			YC056-YL963
0002	20		PA		106-10	23-71-01	D00177		2		D04371P	A01			YL964-YL999, YR301-YR328
0002	20		PA		87-4	23-71-01	D00177		2		D04371P	A01			YN231-YN235
0002	20		PA		87-6	23-71-01	D00177		2		D04371P	A01			YN236-YN501
0003	22		PA		105-5	23-71-01	D00177		55		D04371P	B01			YC051-YC055
0003	22		PA		106-8	23-71-01	D00177		55		D04371P	B01			YC056-YL963
0003	22		PA		106-10	23-71-01	D00177		55		D04371P	B01			YL964-YL999, YR301-YR328
0003	22		PA		87-4	23-71-01	D00177		55		D04371P	B01			YN231-YN235
0003	22		PA		87-6	23-71-01	D00177		55		D04371P	B01			YN236-YN501
0004	22		PA		105-5	23-71-01	D00177		57		D04371P	A02			YC051-YC055
0004	22		PA		106-8	23-71-01	D00177		57		D04371P	A02			YC056-YL963
0004	22		PA		106-10	23-71-01	D00177		57		D04371P	A02			YL964-YL999, YR301-YR328
0004	22		PA		87-4	23-71-01	D00177		57		D04371P	A02			YN231-YN235
0004	22		PA		87-6	23-71-01	D00177		57		D04371P	A02			YN236-YN501
0005	20		PA		4-1	23-71-01	D00177			AA	GD00431	ST..	1		YC051-YL963, YN236-YN501
0005	20		PA		4-3	23-71-01	D00177			AA	GD00431	ST..	1		YL964-YL999, YR301-YR328
0005	20		PA		3-11	23-71-01	D00177			AA	GD00431	ST..	1		YN231-YN235
0006	20		PA		4-1	23-71-01	D00177		17		GD00431	DC..	1		YC051-YL963, YN236-YN501
0006	20		PA		4-3	23-71-01	D00177		17		GD00431	DC..	1		YL964-YL999, YR301-YR328
0006	20		PA		3-11	23-71-01	D00177		17		GD00431	DC..	1		YN231-YN235
0007	24		PK		1-4	23-71-01	D00177		7		D00177		8		ALL
0010	24		PK		19-1	23-27-35	D00177		34	VP	SP00827		9		YN501
0010	24		PK		18-5	23-27-35	D00177		34	VP	SP00827		9		YR301-YR317
0011	24		PK		19-1	23-27-35	D00177		33	VP	SP00829		9		YN501
0011	24		PK		18-5	23-27-35	D00177		33	VP	SP00829		9		YR301-YR317
0012	24		PK		105-5	23-71-01	D00177		12		D04371P	B02			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5430

Page 1

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5431	286A5431				-800 VOICE RECORDER (WITH E6) (continued)											
0012	24		PK		106-8	23-71-01	D00177		12			D04371P	B02			YC056-YL963
0012	24		PK		106-10	23-71-01	D00177		12			D04371P	B02			YL964-YL999, YR301-YR328
0012	24		PK		87-4	23-71-01	D00177		12			D04371P	B02			YN231-YN235
0012	24		PK		87-6	23-71-01	D00177		12			D04371P	B02			YN236-YN501
0013	24		PK		105-5	23-71-01	D00177		13			D04371P	A03			YC051-YC055
0013	24		PK		106-8	23-71-01	D00177		13			D04371P	A03			YC056-YL963
0013	24		PK		106-10	23-71-01	D00177		13			D04371P	A03			YL964-YL999, YR301-YR328
0013	24		PK		87-4	23-71-01	D00177		13			D04371P	A03			YN231-YN235
0013	24		PK		87-6	23-71-01	D00177		13			D04371P	A03			YN236-YN501
0014	24		PK		105-5	23-71-01	D00177		14			D04371P	B03			YC051-YC055
0014	24		PK		106-8	23-71-01	D00177		14			D04371P	B03			YC056-YL963
0014	24		PK		106-10	23-71-01	D00177		14			D04371P	B03			YL964-YL999, YR301-YR328
0014	24		PK		87-4	23-71-01	D00177		14			D04371P	B03			YN231-YN235
0014	24		PK		87-6	23-71-01	D00177		14			D04371P	B03			YN236-YN501
0015	24		PK		105-5	23-71-01	D00177		15			D04371P	A04			YC051-YC055
0015	24		PK		106-8	23-71-01	D00177		15			D04371P	A04			YC056-YL959
0015	24		PK		87-4	23-71-01	D00177		15			D04371P	A04			YN231-YN235
0016	24		PK		105-5	23-71-01	D00177		16			D04371P	B04			YC051-YC055
0016	24		PK		106-8	23-71-01	D00177		16			D04371P	B04			YC056-YL963
0016	24		PK		106-10	23-71-01	D00177		16			D04371P	B04			YL964-YL999, YR301-YR328
0016	24		PK		87-4	23-71-01	D00177		16			D04371P	B04			YN231-YN235
0016	24		PK		87-6	23-71-01	D00177		16			D04371P	B04			YN236-YN501
0017	20		PA		102-4	23-71-01	GD00431		DC..	1		D04371P	A05			YC051-YC055
0017	20		PA		103-7	23-71-01	GD00431		DC..	1		D04371P	A05			YC056-YL999, YR301-YR328
0017	20		PA		84-5	23-71-01	GD00431		DC..	1		D04371P	A05			YN231-YN501
0020	22		PA		21-7	23-71-01	D46623P		7			D40751P	1			YL963
0020	22		PA		22-3	23-71-01	D46623P		7			D40751P	1			YL964-YL999
0020	22		PA		22-4	23-71-01	D46623P		7			D40751P	1			YN236-YR328
0021	14		PA		1-11	23-71-01	D40751P		16			SM00003		W		YL963
0021	14		PA		2-7	23-71-01	D40751P		16			SM00003		W		YL964-YL999
0021	14		PA		2-8	23-71-01	D40751P		16			SM00003		W		YN236-YR328
0024	24		PK		1-9	23-71-01	TB0952Y		B007	1A		D40751P	2			YL963
0024	24		PK		2-2	23-71-01	TB0952Y		B007	1A		D40751P	2			YL964-YL999
0024	24		PK		2-3	23-71-01	TB0952Y		B007	1A		D40751P	2			YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W5430

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W5431	286A5431				-800 VOICE RECORDER (WITH E6) (continued)											
0025	24		PK		2-7	23-71-01	TB0952Y	B007	1A		D13185	11			YL963	
0025	24		PK		2-11	23-71-01	TB0952Y	B007	1A		D13185	11			YL964-YL999, YN236-YR328	
0026	24		PK		2-7	23-71-01	TB0952Y	B005	1A		D13185	10			YL963	
0026	24		PK		2-11	23-71-01	TB0952Y	B005	1A		D13185	10			YL964-YL999, YN236-YR328	
0027	22		PA		0-7	23-71-01	D13185	22			D13185	21			YL963-YL999, YN236-YR328	
0028	22		PA		2-7	23-71-01	GD03951	ST..	1		D13185	3			YL963	
0028	22		PA		3-1	23-71-01	GD03951	ST..	1		D13185	3			YL964-YL999, YN236-YR328	
0029	22		PA		2-7	23-71-01	GD03951	DC..	1		D13185	16			YL963	
0029	22		PA		3-1	23-71-01	GD03951	DC..	1		D13185	16			YL964-YL999, YN236-YR328	
0030	22		PA		20-10	23-71-01	D00177	9	VP		D13185	8			YL963	
0030	22		PA		21-3	23-71-01	D00177	9	VP		D13185	8			YL964-YL999, YN236-YR328	
0031	24		PK		3-10	23-71-01	D13185	12			D10101	6			YL963	
0031	24		PK		4-5	23-71-01	D13185	12			D10101	6			YL964-YL999, YN236-YR328	
0032	24		PK		3-10	23-71-01	D13185	20			D10101	10			YL963	
0032	24		PK		4-5	23-71-01	D13185	20			D10101	10			YL964-YL999, YN236-YR328	
0033	24		PK		2-5	23-71-01	GD03951	DC..	1		D10101	1			YL963	
0033	24		PK		3-0	23-71-01	GD03951	DC..	1		D10101	1			YL964-YL999, YN236-YR328	
0034	24		PK		21-1	23-71-01	D00177	23			D10101	12			YL963	
0034	24		PK		21-7	23-71-01	D00177	23			D10101	12			YL964-YL999	
0034	24		PK		21-8	23-71-01	D00177	23			D10101	12			YN236-YR328	
0035	24		PK		19-10	23-71-01	TB0952Y	A005	1A		D00177	15			YL963	
0035	24		PK		20-1	23-71-01	TB0952Y	A005	1A		D00177	15			YL964-YL999, YN236-YR328	
0036	22		PA		19-10	23-71-01	TB0952Y	A007	1A		D00177	31	VP		YL963	
0036	22		PA		20-1	23-71-01	TB0952Y	A007	1A		D00177	31	VP		YL964-YL999, YN236-YR328	
0037	20		PA		3-0	23-71-01	GD00447	DC..	1		D00177	56	VP		YL963	
0037	20		PA		3-5	23-71-01	GD00447	DC..	1		D00177	56	VP		YL964-YL999, YN236-YR328	

WIRE LIST

D280A108

91-21-11

Section W5430

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W5431	286A5431				-800 VOICE RECORDER (WITH E6) (continued)												
0038	24		PK		0-7	23-71-01		TB0952X	B003	1A		TB0952X	A003	1A		YL963-YL999, YN236-YR328	
0039	24		PK		0-7	23-71-01		TB0952X	B002	1A		TB0952X	A002	1A		YL963-YL999, YN236-YR328	
0040	24		PK		1-5	23-71-01		TB0952Y	B007	1A		TB0952X	A003	1A		YL963	
0040	24		PK		1-7	23-71-01		TB0952Y	B007	1A		TB0952X	A003	1A		YL964-YL999, YN236-YR328	
0041	24		PK		1-5	23-71-01		TB0952Y	B005	1A		TB0952X	B003	1A		YL963	
0041	24		PK		1-7	23-71-01		TB0952Y	B005	1A		TB0952X	B003	1A		YL964-YL999, YN236-YR328	
0042	24		PK		1-5	23-71-01		TB0952Y	B005	1A		TB0952X	B002	1A		YL963	
0042	24		PK		1-7	23-71-01		TB0952Y	B005	1A		TB0952X	B002	1A		YL964-YL999, YN236-YR328	
0043	24		PK		1-5	23-71-01		TB0952Y	A005	1A		TB0952X	A002	1A		YL963	
0043	24		PK		1-7	23-71-01		TB0952Y	A005	1A		TB0952X	A002	1A		YL964-YL999, YN236-YR328	
0044	24		PK		21-4	23-71-01		TB0952Y	B005	1A		D46623P		5		YL963	
0044	24		PK		21-10	23-71-01		TB0952Y	B005	1A		D46623P		5		YL964-YL999, YN236-YR328	
0045	24		PK		21-4	23-71-01		TB0952Y	A005	1A		D46623P		2		YL963	
0045	24		PK		21-10	23-71-01		TB0952Y	A005	1A		D46623P		2		YL964-YL999, YN236-YR328	
0046	22		PA		21-4	23-71-01		TB0952Y	A007	1A		D46623P		3		YL963	
0046	22		PA		21-10	23-71-01		TB0952Y	A007	1A		D46623P		3		YL964-YL999, YN236-YR328	
0047	22		PA		2-10	23-71-01		TB0952Y	A007	1A		D10101		8		YL963	
0047	22		PA		3-3	23-71-01		TB0952Y	A007	1A		D10101		8		YL964-YL999, YN236-YR328	
0050	22		PA		0-10	23-71-01		SM00003		W		D13185		4	VP	YL963-YL999, YN236-YR328	
0055	20		PA		3-5	23-27-35		D00177				GD00447	ST..	1		YR318-YR328	
2001B	24		Y2	AA	105-5	31-22-11		D00177	25		AC	D04371P	B06			YC051-YC055	
2001B	24		Y2	AA	106-8	31-22-11		D00177	25			D04371P	B06			YC056-YL963	
2001B	24		Y2	AA	106-10	31-22-11		D00177	25			D04371P	B06			YL964-YL999, YR301-YR328	
2001B	24		Y2	AA	87-4	31-22-11		D00177	25			D04371P	B06			YN231-YN235	
2001B	24		Y2	AA	87-6	31-22-11		D00177	25			D04371P	B06			YN236-YN501	
2001R	24		Y2	AA	0-0	31-22-11		D00177	26			D04371P	A06			ALL	
2001Z				AA	0-0	31-22-11		D00177			AA	D04371P	PERG	1F		ALL	

WIRE LIST

D280A108

91-21-11

Section W5430

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5431	286A5431				-800 VOICE RECORDER (WITH E6) (continued)										
2002B	24	Y2	AD		105-5	23-51-51	D00177	30			D04371P	B07			YC051-YC055
2002B	24	Y2	AD		106-8	23-51-51	D00177	30			D04371P	B07			YC056-YL963
2002B	24	Y2	AD		106-10	23-51-51	D00177	30			D04371P	B07			YL964-YL999, YR301-YR328
2002B	24	Y2	AD		87-4	23-51-51	D00177	30			D04371P	B07			YN231-YN235
2002B	24	Y2	AD		87-6	23-51-51	D00177	30			D04371P	B07			YN236-YN501
2002R	24	Y2	AD		0-0	23-51-51	D00177	32			D04371P	A07			ALL
2002Z			AD		0-0	23-51-51	D00177			AA	D04371P	B08			ALL
2003B	24	Y2	AC		105-5	23-51-51	D00177	35			D04371P	B09			YC051-YC055
2003B	24	Y2	AC		106-8	23-51-51	D00177	35			D04371P	B09			YC056-YL963
2003B	24	Y2	AC		106-10	23-51-51	D00177	35			D04371P	B09			YL964-YL999, YR301-YR328
2003B	24	Y2	AC		87-4	23-51-51	D00177	35			D04371P	B09			YN231-YN235
2003B	24	Y2	AC		87-6	23-51-51	D00177	35			D04371P	B09			YN236-YN501
2003R	24	Y2	AC		0-0	23-51-51	D00177	37			D04371P	A09			ALL
2003Z			AC		0-0	23-51-51	D00177			AA	D04371P	B10			ALL
2004B	24	Y2	AB		105-5	23-51-51	D00177	41			D04371P	B11			YC051-YC055
2004B	24	Y2	AB		106-8	23-51-51	D00177	41			D04371P	B11			YC056-YL963
2004B	24	Y2	AB		106-10	23-51-51	D00177	41			D04371P	B11			YL964-YL999, YR301-YR328
2004B	24	Y2	AB		87-4	23-51-51	D00177	41			D04371P	B11			YN231-YN235
2004B	24	Y2	AB		87-6	23-51-51	D00177	41			D04371P	B11			YN236-YN501
2004R	24	Y2	AB		0-0	23-51-51	D00177	43			D04371P	A11			ALL
2004Z			AB		0-0	23-51-51	D00177			AA	D04371P	B12			ALL
2005B	24	Y2	AE		105-5	23-71-01	D00177	45			D04371P	B13			YC051-YC055
2005B	24	Y2	AE		106-8	23-71-01	D00177	45			D04371P	B13			YC056-YL963
2005B	24	Y2	AE		106-10	23-71-01	D00177	45			D04371P	B13			YL964-YL999, YR301-YR328
2005B	24	Y2	AE		87-4	23-71-01	D00177	45			D04371P	B13			YN231-YN235
2005B	24	Y2	AE		87-6	23-71-01	D00177	45			D04371P	B13			YN236-YN501
2005R	24	Y2	AE		0-0	23-71-01	D00177	47			D04371P	A13			ALL
2005Z			AE		0-0	23-71-01	D00177			AA	D04371P	B14			ALL
2006B	24	PL	AF		105-5	23-71-01	D00177	5			D04371P	B15			YC051-YC055
2006B	24	PL	AF		106-8	23-71-01	D00177	5			D04371P	B15			YC056-YL963
2006B	24	PL	AF		106-10	23-71-01	D00177	5			D04371P	B15			YL964-YL999, YR301-YR328
2006B	24	PL	AF		87-4	23-71-01	D00177	5			D04371P	B15			YN231-YN235
2006B	24	PL	AF		87-6	23-71-01	D00177	5			D04371P	B15			YN236-YN501
2006R	24	PL	AF		0-0	23-71-01	D00177	6			D04371P	A15			ALL

WIRE LIST

D280A108

91-21-11

Section W5430

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5431		286A5431			-800 VOICE RECORDER (WITH E6) (continued)											
I	2007B	24		PL	AG	105-5	23-71-01	D00177	24	VP		D04371P	B16			YC051-YC055
	2007B	24		PL	AG	106-8	23-71-01	D00177	24	VP		D04371P	B16			YC056-YD157
	2007B	24		PL	AG	106-8	23-71-01	D00177	24			D04371P	B16			YD158-YL959
	2007B	24		PL	AG	87-4	23-71-01	D00177	24			D04371P	B16			YN231-YN235
I	2007R	24		PL	AG	0-0	23-71-01	D00177	23	VP		D04371P	A16			YC051-YD157
	2007R	24		PL	AG	0-0	23-71-01	D00177	23			D04371P	A16			YD158-YL959, YN231-YN235
I	2008B	24		Y2	AH	18-5	23-27-35	D00177	33	VP		SP00829		V		YR318-YR328
I	2008R	24		Y2	AH	0-0	23-27-35	D00177	34	VP		SP00827		V		YR318-YR328
I	2008Z				AH	0-0	23-27-35	D00177			AC	SP00827	REF		AB	YR318-YR328

WIRE LIST

D280A108

91-21-11

Section W5430

Page 6 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To								
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I	W5457	286A5457			AUTOPILOT E1-4 TO CONTROL STAND - SYSTEM B											
	0001	22	PA		14-7	22-31-51	D05971J		1			SP03097		S		YC051-YC064
I	0001	22	PA		14-10	22-31-51	D05971J		1			SP03097		S		YC065-YR328
I	0002	22	PA		1-7	22-11-31	GD05010	ST..	E			D01713			AA	ALL
	0005	22	PA		16-1	22-11-14	D05971J		5			SM00001		S		YC051-YC064
I	0005	22	PA		16-6	22-11-14	D05971J		5			SM00001		S		YC065-YR328
	0006	22	PA		16-1	22-11-14	D05971J		6			SM00002		S		YC051-YC064
I	0006	22	PA		16-6	22-11-14	D05971J		6			SM00002		S		YC065-YR328
	0011	20	PA		13-11	22-11-12	D05971J		11			TB0805Y	B009	1A		YC051-YC064
I	0011	20	PA		13-10	22-11-12	D05971J		11			TB0805Y	B009	1A		YC065-YR328
	0012	20	PA		15-8	22-11-12	D05971J		12			TB0806X	A013	1A		YC051-YC064
I	0012	20	PA		16-2	22-11-12	D05971J		12			TB0806X	A013	1A		YC065-YR328
I	0015	20	PA		2-4	22-11-11	D01713		5			GD00287	ST..	E		ALL
I	0025	20	PA		1-6	22-11-11	D01673		5			GD00891	ST..	E		ALL
	0035	20	PA		2-0	22-11-11	D01675		5			GD01053	ST..	E		YC051-YC064
I	0035	20	PA		2-7	22-11-11	D01675		5			GD01053	ST..	E		YC065-YR328
	0101	22	PA		1-1	22-11-14	D08315P		1			SM00001		S		YC051-YC064
I	0101	22	PA		0-7	22-11-14	D08315P		1			SM00001		S		YC065-YR328
	0102	22	PA		1-1	22-11-14	D08315P		2			SM00002		S		YC051-YC064
I	0102	22	PA		0-7	22-11-14	D08315P		2			SM00002		S		YC065-YR328
	0105	22	PA		16-7	22-31-51	D08315P		5			D05971J	2			YC051-YC064
I	0105	22	PA		16-6	22-31-51	D08315P		5			D05971J	2			YC065-YR328
	0106	22	PA		5-1	22-31-51	D08315P		6			SP03097		S		YC051-YC064
I	0106	22	PA		5-2	22-31-51	D08315P		6			SP03097		S		YC065-YR328
	0107	22	PA		2-10	22-31-51	D08315P		7			GD00803	DC..	1A		YC051-YC064
I	0107	22	PA		2-9	22-31-51	D08315P		7			GD00803	DC..	1A		YC065-YR328
	0108	22	PA		5-1	22-31-51	D08315P		8			SP03101		S		YC051-YC064
I	0108	22	PA		5-2	22-31-51	D08315P		8			SP03101		S		YC065-YR328
	0111	22	PA		1-1	22-11-14	D08315P		11			SM00001		S		YC051-YC064
I	0111	22	PA		0-7	22-11-14	D08315P		11			SM00001		S		YC065-YR328
	0112	22	PA		1-1	22-11-14	D08315P		12			SM00002		S		YC051-YC064
I	0112	22	PA		0-7	22-11-14	D08315P		12			SM00002		S		YC065-YR328
	2007B	22	PB	AG	13-1	22-11-11	D05971J		8			D01675	1			YC051-YC064
I	2007B	22	PB	AG	12-6	22-11-11	D05971J		8			D01675	1			YC065-YR328
I	2007R	22	PB	AG	0-0	22-11-11	D05971J		7			D01675	4			ALL
	2009B	22	PB	AI	13-1	22-12-41	D05971J		10			D01675	3			YC051-YC064
I	2009B	22	PB	AI	12-6	22-12-41	D05971J		10			D01675	3			YC065-YR328
I	2009R	22	PB	AI	0-0	22-12-41	D05971J		9			D01675	2			ALL
I	2014B	22	PB	AN	16-6	22-11-11	D05971J		15			D01713	1			ALL
I	2014R	22	PB	AN	0-0	22-11-11	D05971J		14			D01713	4			ALL

WIRE LIST

D280A108

91-21-11

Section W5450

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity

W5457		286A5457		AUTOPILOT E1-4 TO CONTROL STAND - SYSTEM B (continued)											
2016B	22	X2	AR		16-6	22-11-31	D05971J	17			D01713	3			ALL
2016R	22	X2	AR		0-0	22-11-31	D05971J	16			D01713	2			ALL
2016Z			AR		0-0	22-11-31	D05971J	DED			D01713		AA		ALL
2018B	22	PB	AT		15-5	22-11-11	D05971J	19			D01673	4			ALL
2018R	22	PB	AT		0-0	22-11-11	D05971J	18			D01673	1			ALL
2020B	22	PB	AV		15-5	22-12-41	D05971J	21			D01673	3			ALL
2020R	22	PB	AV		0-0	22-12-41	D05971J	20			D01673	2			ALL

WIRE LIST

D280A108

91-21-11

Section W5450

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5461	286A5461			FLIGHT RECORDER E3-2 SHELF TO E1-1 AND E5-2 SHELF											
0001	24		PK		32-10	31-35-01	D45261J		A04		D43261P		A04		YC051-YC055
0001	24		PK		33-5	31-35-01	D45261J		A04		D43261P		A04		YC056-YR328
0003	24		PK		32-10	31-35-01	D45261J		A05		D43261P		A03		YC051-YC055
0003	24		PK		33-5	31-35-01	D45261J		A05		D43261P		A03		YC056-YR328
0004	24		PK		32-10	31-35-01	D45261J		A06		D43261P		A06		YC051-YC055
0004	24		PK		33-5	31-35-01	D45261J		A06		D43261P		A06		YC056-YR328
0006	22		PA		13-9	34-61-18	D45261J		B18		D43211P		A06		YC051-YC058
0006	22		PA		13-9	31-32-15	D45261J		B18		D43211P		A06		YC059-YN235
0006	22		PA		13-10	31-32-15	D45261J		B18		D43211P		A06		YN236-YR328
0008	22		PA		32-10	34-61-12	D41561J		A14		D42261P		A14		YC051-YC055
0008	22		PA		33-5	34-61-12	D41561J		A14		D42261P		A14		YC056-YR328
0009	24		B6		22-11	31-31-15	D42361P		B07		D43211P		B07		YC051-YC055
0009	24		B6		23-6	31-31-15	D42361P		B07		D43211P		B07		YC056-YN235
0009	24		B6		23-5	31-31-15	D42361P		B07		D43211P		B07		YN236-YR328
0010	20		CQ		22-11	27-31-11	D42361P		A08		D43211P		A08		YC051-YC055
0010	20		CQ		23-6	27-31-11	D42361P		A08		D43211P		A08		YC056-YN235
0010	20		CQ		23-5	27-31-11	D42361P		A08		D43211P		A08		YN236-YR328
0012	22		PA		24-6	23-51-51	D46461P		A13		D44161P		A08		YC051-YC055
0012	22		PA		25-7	23-51-51	D46461P		A13		D44161P		A08		YC056-YR328
0013	22		CQ		24-6	23-51-51	D46461P		B08		D44161P		A20		YC051-YC055
0013	22		CQ		25-7	23-51-51	D46461P		B08		D44161P		A20		YC056-YR328
0015	22		CQ		24-5	22-14-11	D44161P		A15		D43211P		A15		YC051-YC055
0015	22		CQ		25-7	22-14-11	D44161P		A15		D43211P		A15		YC056-YR328
0018	22		PA		22-11	34-21-15	D42361P		A07		D43211P		A07		YC051-YC055
0018	22		PA		23-6	34-21-15	D42361P		A07		D43211P		A07		YC056-YN235
0018	22		PA		23-5	34-21-15	D42361P		A07		D43211P		A07		YN236-YR328
0034	20		PA		13-10	34-61-22	D46461P		B11		D45261J		A14		ALL
0037	22		PA		13-9	34-21-16	D46461P		B17		D41561J		B17		YC051-YN235
0037	22		PA		13-10	34-21-16	D46461P		B17		D41561J		B17		YN236-YR328
0038	22		PA		13-9	34-21-16	D46461P		B18		D41561J		B18		YC051-YN235
0038	22		PA		13-10	34-21-16	D46461P		B18		D41561J		B18		YN236-YR328
0045	24		PK		22-11	SPARE	D43211P		B15		D42361P		B11		YC051-YC055
0045	24		PK		23-6	SPARE	D43211P		B15		D42361P		B11		YC056-YN235
0045	24		PK		23-5	SPARE	D43211P		B15		D42361P		B11		YN236-YR328
0046	24		PK		22-11	31-31-17	D43211P		B08		D42361P		B08		YC051-YC055
0046	24		PK		23-6	31-31-17	D43211P		B08		D42361P		B08		YC056-YN235
0046	24		PK		23-5	31-31-17	D43211P		B08		D42361P		B08		YN236-YR328
0048	24		PK		10-1	31-31-17	D42361P		B15		D44161P		B15		YC051-YC055
0048	24		PK		11-0	31-31-17	D42361P		B15		D44161P		B15		YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W5460

Page 1

Nov 12/2012

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5461	286A5461			FLIGHT RECORDER E3-2 SHELF TO E1-1 AND E5-2 SHELF (continued)											
0056	24		PK		22-11	31-31-15	D42361P	A11			D43211P	B10			YC051-YC055
0056	24		PK		23-6	31-31-15	D42361P	A11			D43211P	B10			YC056-YN235
0056	24		PK		23-5	31-31-15	D42361P	A11			D43211P	B10			YN236-YR328
0057	24		PK		10-1	SPARE	D42361P	B06			D44161P	B04			YC051-YC055
0057	24		PK		11-0	SPARE	D42361P	B06			D44161P	B04			YC056-YR328
0058	24		PK		10-1	SPARE	D42361P	A06			D44161P	A06			YC051-YC055
0058	24		PK		11-0	SPARE	D42361P	A06			D44161P	A06			YC056-YR328
0059	24		PK		32-10	31-31-17	D42261P	B10			D41561J	B14			YC051-YC055
0059	24		PK		33-5	31-31-17	D42261P	B10			D41561J	B14			YC056-YD157
0059	24		PK		33-5	SPARE	D42261P	B10			D41561J	B14			YD158-YD170
0061	24		PK		34-6	34-61-17	D44161P	A09			D41561J	A09			YC051-YC055
0061	24		PK		35-8	34-61-17	D44161P	A09			D41561J	A09			YC056-YR328
0062	24		PK		34-6	34-61-17	D44161P	A10			D41561J	A10			YC051-YC055
0062	24		PK		35-8	34-61-17	D44161P	A10			D41561J	A10			YC056-YR328
0063	24		PK		34-6	34-61-17	D44161P	A17			D41561J	A17			YC051-YC055
0063	24		PK		35-8	34-61-17	D44161P	A17			D41561J	A17			YC056-YR328
0064	24		PK		34-6	34-61-17	D44161P	A18			D41561J	A18			YC051-YC055
0064	24		PK		35-8	34-61-17	D44161P	A18			D41561J	A18			YC056-YR328
0065	22		PA		34-6	34-61-17	D44161P	A19			D41561J	A19			YC051-YC055
0065	22		PA		35-8	34-61-17	D44161P	A19			D41561J	A19			YC056-YR328
0066	22		PA		5-0	31-35-03	D43217P	A01			D43049P	A01			YN236-YR328
0067	24		PK		10-0	21-51-14	D44161P	A07			D42261P	B06			YC051-YC055
0067	24		PK		10-11	21-51-14	D44161P	A07			D42261P	B06			YC056-YN235
0067	24		PK		10-10	21-51-14	D44161P	A07			D42261P	B06			YN236-YR328
0068	24		PK		5-0	31-35-03	D43217P	A10			D43049P	A10			YN236-YR328
0069	24		PK		5-0	31-35-03	D43217P	B01			D43049P	B01			YN236-YR328
0071	24		PK		32-10	31-31-17	D42261P	B05			D41561J	A16			YC051-YC055
0071	24		PK		33-5	31-31-17	D42261P	B05			D41561J	A16			YC056-YD157
0071	24		PK		33-5	SPARE	D42261P	B05			D41561J	A16			YD158-YD170
0073	24		PK		22-11	SPARE	D43211P	A14			D42361P	A14			YC051-YC055
0073	24		PK		23-6	SPARE	D43211P	A14			D42361P	A14			YC056-YN235
0073	24		PK		23-5	SPARE	D43211P	A14			D42361P	A14			YN236-YR328
0074	24		PK		22-11	SPARE	D43211P	B13			D42361P	B13			YC051-YC055
0074	24		PK		23-6	SPARE	D43211P	B13			D42361P	B13			YC056-YN235
0074	24		PK		23-5	SPARE	D43211P	B13			D42361P	B13			YN236-YR328
0076	22		CQ		35-8	34-21-22	D44161P	B20			D45261J	B20			YL951-YL999
0076	22		CQ		35-8	34-21-22	D45261J	B20			D44161P	B20			YN231-YN235
0076	22		CQ		35-9	34-21-22	D44161P	B20			D45261J	B20			YN236-YR328
0077	22		PA		35-8	34-21-12	D44161P	B19			D45261J	B19			YL951-YL999

WIRE LIST

D280A108

91-21-11

Section W5460

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W5461	286A5461				FLIGHT RECORDER E3-2 SHELF TO E1-1 AND E5-2 SHELF (continued)												
0077	22		PA		35-8	34-21-12	D45261J	B19			D44161P	B19			YN231-YN235		
0077	22		CQ		35-9	34-21-12	D44161P	B19			D45261J	B19			YN236-YR328		
0078	22		PA		33-5	SPARE	D41561J	B16			D42261P	A13			YN231-YN235		
0081	24		PK		22-10	27-81-31	D43261P	B03			D46461P	B05			YC051-YC055		
0081	24		PK		23-4	27-81-31	D43261P	B03			D46461P	B05			YC056-YR328		
0082	24		PK		22-10	27-81-31	D46461P	A05			D43261P	A05			YC051-YC055		
0082	24		PK		23-4	27-81-31	D46461P	A05			D43261P	A05			YC056-YR328		
0083	24		PK		11-0	SPARE	D44161P	A16			D42361P	A20			YN231-YN235		
0085	22		PA		33-5	SPARE	D45261J	B11			D43261P	B06			YN231-YN235		
0086	24		PK		10-11	SPARE	D42261P	A06			D44161P	A04			YL951-YL999		
0087	24		PK		5-0	31-35-03	D43217P	B02			D43049P	B02			YN236-YR328		
0088	24		PK		5-0	31-35-03	D43217P	B03			D43049P	B03			YN236-YR328		
0089	24		PK		5-0	31-35-03	D43217P	B04			D43049P	B04			YN236-YR328		
0100	24		B6		25-7	21-51-11	D46461P	A06			D44161P	B10			YD158-YR328		
0501	20		PA		22-11	27-53-11	D43211P	A05			D42361P	A05			YC051-YC055		
0501	20		PA		23-6	27-53-11	D43211P	A05			D42361P	A05			YC056-YN235		
0501	20		PA		23-5	27-53-11	D43211P	A05			D42361P	A05			YN236-YR328		
0502	20		PA		22-11	27-53-11	D43211P	A10			D42361P	B12			YC051-YC055		
0502	20		PA		23-6	27-53-11	D43211P	A10			D42361P	B12			YC056-YN235		
0502	20		PA		23-5	27-53-11	D43211P	A10			D42361P	B12			YN236-YR328		
0503	20		PA		22-11	27-53-11	D43211P	B14			D42361P	B14			YC051-YC055		
0503	20		PA		23-6	27-53-11	D43211P	B14			D42361P	B14			YC056-YN235		
0503	20		PA		23-5	27-53-11	D43211P	B14			D42361P	B14			YN236-YR328		
2001B	24		Y2	AA	32-10	31-35-01	D45261J	B01			D43261P	B01			YC051-YC055		
2001B	24		Y2	AA	33-5	31-35-01	D45261J	B01			D43261P	B01			YC056-YR328		
2001R	24		Y2	AA	0-0	31-35-01	D45261J	A01			D43261P	A01			ALL		
2001Z				AA	0-0	31-35-01	D45261J	PERG	1F		D43261P	PERG	1F		ALL		
2002B	24		Y2	AB	32-10	31-35-01	D45261J	B02			D43261P	B02			YC051-YC055		
2002B	24		Y2	AB	33-5	31-35-01	D45261J	B02			D43261P	B02			YC056-YR328		
2002R	24		Y2	AB	0-0	31-35-01	D45261J	A02			D43261P	A02			ALL		
2002Z				AB	0-0	31-35-01	D45261J	PERG	1F		D43261P	PERG	1F		ALL		
2003B	24		Y2	AC	32-10	SPARE	D41561J	B01			D42261P	B01			YC051-YC055		
2003B	24		Y2	AC	33-5	SPARE	D41561J	B01			D42261P	B01			YC056-YR328		
2003R	24		Y2	AC	0-0	SPARE	D41561J	A01			D42261P	A01			ALL		
2003Z				AC	0-0	SPARE	D41561J	PERG	1F		D42261P	PERG	1F		ALL		
2004B	24		Y2	AD	22-11	22-31-52	D43211P	B01			D42361P	B01			YC051-YC055		
2004B	24		Y2	AD	23-6	22-31-52	D43211P	B01			D42361P	B01			YC056-YN235		
2004B	24		Y2	AD	23-5	22-31-52	D43211P	B01			D42361P	B01			YN236-YR328		
2004R	24		Y2	AD	0-0	22-31-52	D43211P	A01			D42361P	A01			ALL		

WIRE LIST

D280A108

91-21-11

Section W5460

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Diagram	From				To				Effectivity
	Wire No.	GA	CO TY			Fam	FT-IN	Equip	Term	Type	Splice	Equip	Term	
W5461	286A5461			FLIGHT RECORDER E3-2 SHELF TO E1-1 AND E5-2 SHELF (continued)										
2004Z				AD	0-0	22-31-52	D43211P	PERG	1F		D42361P	PERG	1F	ALL
2005B	24	Y2	AE		32-10	31-35-02	D43261P	A10			D45261J	A10		YC051-YC055
2005B	24	Y2	AE		33-5	31-35-02	D43261P	A10			D45261J	A10		YC056-YR328
2005R	24	Y2	AE		0-0	31-35-02	D43261P	A09			D45261J	A09		ALL
2005Z			AE		0-0	31-35-02	D43261P	PERG	1F		D45261J	PERG	1F	ALL
2006B	24	Y2	AF		22-11	34-49-11	D43211P	B03			D42361P	B03		YC051-YC055
2006B	24	Y2	AF		23-6	34-49-11	D43211P	B03			D42361P	B03		YC056-YN235
2006B	24	Y2	AF		23-5	34-49-11	D43211P	B03			D42361P	B03		YN236-YR328
2006R	24	Y2	AF		0-0	34-49-11	D43211P	A03			D42361P	A03		ALL
2006Z			AF		0-0	34-49-11	D43211P	PERG	1F		D42361P	PERG	1F	ALL
2007B	22	X2	AG		22-11	34-21-15	D43211P	B04			D42361P	B04		YC051-YC055
2007B	22	X2	AG		23-6	34-21-15	D43211P	B04			D42361P	B04		YC056-YN235
2007B	22	X2	AG		23-5	34-21-15	D43211P	B04			D42361P	B04		YN236-YR328
2007R	22	X2	AG		0-0	34-21-15	D43211P	A04			D42361P	A04		ALL
2007Z			AG		0-0	34-21-15	D43211P	PERG	1F		D42361P	PERG	1F	ALL
2008B	24	Y2	JH		22-11	34-45-11	D43211P	B02			D42361P	B02		YC051-YC055
2008B	24	Y2	JH		23-6	34-45-11	D43211P	B02			D42361P	B02		YC056-YN235
2008B	24	Y2	JH		23-5	34-45-11	D43211P	B02			D42361P	B02		YN236-YR328
2008R	24	Y2	JH		0-0	34-45-11	D43211P	A02			D42361P	A02		ALL
2008Z			JH		0-0	34-45-11	D43211P	PERG	1F		D42361P	PERG	1F	ALL
2009B	22	X2	JI		32-10	34-61-15	D45261J	B07			D43261P	B07		YC051-YC055
2009B	22	X2	JI		33-5	34-61-15	D45261J	B07			D43261P	B07		YC056-YR328
2009R	22	X2	JI		0-0	34-61-15	D45261J	A07			D43261P	A07		ALL
2009Z			JI		0-0	34-61-15	D45261J	PERG	1F		D43261P	PERG	1F	ALL
2010B	24	Y2	JJ		32-10	34-61-14	D45261J	B08			D43261P	B08		YC051-YC055
2010B	24	Y2	JJ		33-5	34-61-14	D45261J	B08			D43261P	B08		YC056-YR328
2010R	24	Y2	JJ		0-0	34-61-14	D45261J	A08			D43261P	A08		ALL
2010Z			JJ		0-0	34-61-14	D45261J	PERG	1F		D43261P	PERG	1F	ALL
2011B	24	Y2	JK		32-10	SPARE	D41561J	B15			D42261P	B15		YC051-YC055
2011B	24	Y2	JK		33-5	SPARE	D41561J	B15			D42261P	B15		YC056-YR328
2011R	24	Y2	JK		0-0	SPARE	D41561J	A15			D42261P	A15		ALL
2011Z			JK		0-0	SPARE	D41561J	PERG	1F		D42261P	PERG	1F	ALL
2012B	24	Y2	JL		33-5	SPARE	D41561J	B02			D42261P	B02		YN231-YN235
2012R	24	Y2	JL		0-0	SPARE	D41561J	A02			D42261P	A02		YN231-YN235
2012Z			JL		0-0	SPARE	D41561J	PERG	1F		D42261P	PERG	1F	YN231-YN235
2013B	24	Y2	JM		32-10	34-21-13	D41561J	B03			D42261P	B03		YC051-YC055
2013B	24	Y2	JM		33-5	34-21-13	D41561J	B03			D42261P	B03		YC056-YR328
2013R	24	Y2	JM		0-0	34-21-13	D41561J	A03			D42261P	A03		ALL
2013Z			JM		0-0	34-21-13	D41561J	PERG	1F		D42261P	PERG	1F	ALL

WIRE LIST

D280A108

91-21-11

Section W5460

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5461	286A5461				FLIGHT RECORDER E3-2 SHELF TO E1-1 AND E5-2 SHELF (continued)										
2014B	24	Y2	JN		32-10	34-21-13	D41561J	B04			D42261P	B04			YC051-YC055
2014B	24	Y2	JN		33-5	34-21-13	D41561J	B04			D42261P	B04			YC056-YR328
2014R	24	Y2	JN		0-0	34-21-13	D41561J	A04			D42261P	A04			ALL
2014Z			JN		0-0	34-21-13	D41561J	PERG	1F		D42261P	PERG	1F		ALL
2015B	24	Y2	JO		13-9	22-11-51	D41561J	B05			D43211P	B11			ALL
2015R	24	Y2	JO		0-0	22-11-51	D41561J	A05			D43211P	A11			ALL
2015Z			JO		0-0	22-11-51	D41561J	PERG	1F		D43211P	PERG	1F		ALL
2016B	24	Y2	JP		13-9	22-11-51	D41561J	B06			D43211P	B12			ALL
2016R	24	Y2	JP		0-0	22-11-51	D41561J	A06			D43211P	A12			ALL
2016Z			JP		0-0	22-11-51	D41561J	PERG	1F		D43211P	PERG	1F		ALL
2017B	24	Y2	JQ		32-10	34-21-14	D41561J	B07			D42261P	B07			YC051-YC055
2017B	24	Y2	JQ		33-5	34-21-14	D41561J	B07			D42261P	B07			YC056-YR328
2017R	24	Y2	JQ		0-0	34-21-14	D41561J	A07			D42261P	A07			ALL
2017Z			JQ		0-0	34-21-14	D41561J	PERG	1F		D42261P	PERG	1F		ALL
2018B	24	Y2	JR		34-6	34-21-14	D44161P	B11			D41561J	B11			YC051-YC055
2018B	24	Y2	JR		35-8	34-21-14	D44161P	B11			D41561J	B11			YC056-YD157
2018B	24	Y2	JR		35-8	SPARE	D44161P	B11			D41561J	B11			YD158-YR328
2018R	24	Y2	JR		0-0	34-21-14	D44161P	A11			D41561J	A11			YC051-YD157
2018R	24	Y2	JR		0-0	SPARE	D44161P	A11			D41561J	A11			YD158-YR328
2018Z			JR		0-0	34-21-14	D44161P	PERG	1F		D41561J	PERG	1F		YC051-YD157
2018Z			JR		0-0	SPARE	D44161P	PERG	1F		D41561J	PERG	1F		YD158-YR328
2019B	24	Y2	JS		14-0	31-22-11	D42311P	B07			D41561J	B12			ALL
2019R	24	Y2	JS		0-0	31-22-11	D42311P	A07			D41561J	A12			ALL
2019Z			JS		0-0	31-22-11	D42311P	PERG	1F		D41561J	PERG	1F		ALL
2020B	24	Y2	JT		14-0	31-22-11	D41561J	B13			D42311P	B08			ALL
2020R	24	Y2	JT		0-0	31-22-11	D41561J	A13			D42311P	A08			ALL
2020Z			JT		0-0	31-22-11	D41561J	PERG	1F		D42311P	PERG	1F		ALL
2021B	24	Y2	JV		22-11	27-81-41	D43211P	B16			D42361P	B16			YC051-YC055
2021B	24	Y2	JV		23-6	27-81-41	D43211P	B16			D42361P	B16			YC056-YN235
2021B	24	Y2	JV		23-5	27-81-41	D43211P	B16			D42361P	B16			YN236-YR328
2021R	24	Y2	JV		0-0	27-81-41	D43211P	A16			D42361P	A16			ALL
2021Z			JV		0-0	27-81-41	D43211P	PERG	1F		D42361P	PERG	1F		ALL
2022B	24	Y2	JW		34-6	31-22-11	D41561J	B08			D44161P	B03			YC051-YC055
2022B	24	Y2	JW		35-8	31-22-11	D41561J	B08			D44161P	B03			YC056-YR328
2022R	24	Y2	JW		0-0	31-22-11	D41561J	A08			D44161P	A03			ALL
2022Z			JW		0-0	31-22-11	D41561J	PERG	1F		D44161P	PERG	1F		ALL
2023B	24	Y2	JX		10-1	31-22-11	D42361P	B17			D44161P	B01			YC051-YC055
2023B	24	Y2	JX		11-0	31-22-11	D42361P	B17			D44161P	B01			YC056-YR328
2023R	24	Y2	JX		0-0	31-22-11	D42361P	A17			D44161P	A01			ALL

WIRE LIST

D280A108

91-21-11

Section W5460

Page 5

Nov 12/2012

Bundle No.	Part Number			Description	From			To							
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5461	286A5461			FLIGHT RECORDER E3-2 SHELF TO E1-1 AND E5-2 SHELF (continued)											
2023Z				JX	0-0	31-22-11	D42361P	PERG	1F		D44161P	PERG	1F		ALL
2024B	24	M5		UH	24-6	34-45-21	D46461P	A15			D44161P	A13			YC051-YC055
2024B	24	M5		UH	25-7	34-45-21	D46461P	A15			D44161P	A13			YC056-YR328
2024R	24	M5		UH	0-0	34-45-21	D46461P	A14			D44161P	A12			ALL
2024ZI				UH	0-0	34-45-21	D46461P	A16			D44161P	A14			ALL
2024ZO				UH	0-0	34-45-21	D46461P	PERG	1F		D44161P	PERG	1F		ALL
2028B	22	X2		UL	32-11	23-32-21	D42261P	B20			D45261J	A20			YC051-YC055
2028B	22	X2		UL	33-6	23-32-21	D42261P	B20			D45261J	A20			YC056-YD157
2028B	22	X2		UL	33-6	SPARE	D42261P	B20			D45261J	A20			YD158-YD170
2028R	22	X2		UL	0-0	23-32-21	D42261P	B19			D45261J	A19			YC051-YD157
2028R	22	X2		UL	0-0	SPARE	D42261P	B19			D45261J	A19			YD158-YD170
2028Z				UL	0-0	23-32-21	D42261P	PERG	1F		D45261J	PERG	1F		YC051-YD157
2028Z				UL	0-0	SPARE	D42261P	PERG	1F		D45261J	PERG	1F		YD158-YD170
2029B	24	Y2		KD	34-6	SPARE	D44161P	B13			D45261J	B15			YC051-YC055
2029B	24	Y2		KD	35-8	SPARE	D44161P	B13			D45261J	B15			YC056-YN235
2029B	24	Y2		KD	35-9	SPARE	D44161P	B13			D45261J	B15			YN236-YR328
2029R	24	Y2		KD	0-0	SPARE	D44161P	B12			D45261J	B14			ALL
2029Z				KD	0-0	SPARE	D44161P	PERG	1F		D45261J	PERG	1F		ALL
2030B	24	Y2		KE	34-6	SPARE	D44161P	B17			D45261J	B17			YC051-YC055
2030B	24	Y2		KE	35-8	SPARE	D44161P	B17			D45261J	B17			YC056-YN235
2030B	24	Y2		KE	35-9	SPARE	D44161P	B17			D45261J	B17			YN236-YR328
2030R	24	Y2		KE	0-0	SPARE	D44161P	B16			D45261J	B16			ALL
2030Z				KE	0-0	SPARE	D44161P	PERG	1F		D45261J	PERG	1F		ALL
2031B	24	Y2		KF	24-6	SPARE	D44161P	B07			D46461P	B07			YC051-YC055
2031B	24	Y2		KF	25-7	SPARE	D44161P	B07			D46461P	B07			YC056-YL959, YN231-YN235
2031R	24	Y2		KF	0-0	SPARE	D44161P	B06			D46461P	B06			YC051-YL959, YN231-YN235
2031Z				KF	0-0	SPARE	D44161P	PERG	1F		D46461P	PERG	1F		YC051-YL959, YN231-YN235
2032B	24	Y2		KG	32-10	34-61-15	D43261P	B10			D45261J	B10			YC051-YC055
2032B	24	Y2		KG	33-5	34-61-15	D43261P	B10			D45261J	B10			YC056-YD170
2032B	24	Y2		KG	33-5	SPARE	D43261P	B10			D45261J	B10			YL951-YR328
2032R	24	Y2		KG	0-0	34-61-15	D43261P	B09			D45261J	B09			YC051-YD170
2032R	24	Y2		KG	0-0	SPARE	D43261P	B09			D45261J	B09			YL951-YR328
2032Z				KG	0-0	34-61-15	D43261P	PERG	1F		D45261J	PERG	1F		YC051-YD170
2032Z				KG	0-0	SPARE	D43261P	PERG	1F		D45261J	PERG	1F		YL951-YR328
2033B	24	Y2		AH	32-10	31-33-01	D43261P	A19			D45261J	B06			YC051-YC055
2033B	24	Y2		AH	33-5	31-33-01	D43261P	A19			D45261J	B06			YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W5460

Page 6

Nov 12/2012



WIRE LIST
D280A108

91-21-11
Section W5460
Page 7
Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5461	286A5461			FLIGHT RECORDER E3-2 SHELF TO E1-1 AND E5-2 SHELF (continued)											
2101B	22	PB	MA		33-5	27-32-11	D45261J	B13			D43261P	B14			YC056-YR328
2101R	22	PB	MA		0-0	27-32-11	D45261J	B12			D43261P	A14			ALL
2102B	24	Y2	GG		22-11	22-11-51	D42361P	B19			D43211P	B20			YC051-YC055
2102B	24	Y2	GG		23-6	22-11-51	D42361P	B19			D43211P	B20			YC056-YN235
2102B	24	Y2	GG		23-5	22-11-51	D42361P	B19			D43211P	B20			YN236-YR328
2102R	24	Y2	GG		0-0	22-11-51	D42361P	A19			D43211P	B19			ALL
2102Z			GG		0-0	22-11-51	D42361P	PERG	1F		D43211P	PERG	1F		ALL
2103B	24	Y2	MC		23-1	SPARE	D42311P	A10			D42261P	B12			YC051-YC055
2103B	24	Y2	MC		23-8	SPARE	D42311P	A10			D42261P	B12			YC056-YN235
2103B	24	Y2	MC		23-7	SPARE	D42311P	A10			D42261P	B12			YN236-YR328
2103R	24	Y2	MC		0-0	SPARE	D42311P	A09			D42261P	B11			ALL
2103Z			MC		0-0	SPARE	D42311P	PERG	1F		D42261P	PERG	1F		ALL
2104B	24	Y2	MD		10-1	SPARE	D44161P	A05			D42361P	B05			YC051-YC055
2104B	24	Y2	MD		11-0	SPARE	D44161P	A05			D42361P	B05			YC056-YC058
2104B	22	X2	MD		33-5	31-32-15	D41561J	B10			D43261P	B05			YC059-YR328
2104R	24	Y2	MD		0-0	SPARE	D44161P	A04			D42361P	A12			YC051-YC058
2104R	22	X2	MD		0-0	31-32-15	D41561J	B09			D43261P	B04			YC059-YR328
2104Z			MD		0-0	SPARE	D44161P	PERG	1F		D42361P	PERG	1F		YC051-YC058
2104Z			MD		0-0	31-32-15	D41561J	PERG	1F		D43261P	PERG	1F		YC059-YR328
2106B	24	Y2	MF		13-9	34-61-18	D45261J	A13			D43211P	A20			YC051-YC058
2106B	24	Y2	MF		13-9	31-32-15	D45261J	A13			D43211P	A20			YC059-YN235
2106B	24	Y2	MF		13-10	31-32-15	D45261J	A13			D43211P	A20			YN236-YR328
2106R	24	Y2	MF		0-0	34-61-18	D45261J	A12			D43211P	A19			YC051-YC058
2106R	24	Y2	MF		0-0	31-32-15	D45261J	A12			D43211P	A19			YC059-YR328
2106Z			MF		0-0	34-61-18	D45261J	PERG	1F		D43211P	PERG	1F		YC051-YC058
2106Z			MF		0-0	31-32-15	D45261J	PERG	1F		D43211P	PERG	1F		YC059-YR328
2113B	24	Y2	EM		23-6	27-32-12	D46461P	B01			D42361P	A15			YD158-YR328
2113R	24	Y2	EM		0-0	27-32-12	D46461P	A01			D42361P	A13			YD158-YR328
2113Z			EM		0-0	27-32-12	D46461P	PERG	1F		D42361P	PERG	1F		YD158-YR328
2130B	24	Y2	FE		25-10	21-31-23	D42311P	A06			D44161P	B05			YD158-YR328
2130R	24	Y2	FE		0-0	21-31-23	D42311P	A05			D44161P	A05			YD158-YR328
2130Z			FE		0-0	21-31-23	D42311P	PERG	1F		D44161P	PERG	1F		YD158-YR328
2131B	24	Y2	FF		25-10	21-31-23	D44161P	B18			D42311P	B10			YD158-YR328
2131R	24	Y2	FF		0-0	21-31-23	D44161P	B14			D42311P	B09			YD158-YR328
2131Z			FF		0-0	21-31-23	D44161P	PERG	1F		D42311P	PERG	1F		YD158-YR328
2209B	24	Y2	PA		22-11	22-11-51	D43211P	B09			D42361P	B09			YC051-YC055
2209B	24	Y2	PA		23-6	22-11-51	D43211P	B09			D42361P	B09			YC056-YN235
2209B	24	Y2	PA		23-5	22-11-51	D43211P	B09			D42361P	B09			YN236-YR328
2209R	24	Y2	PA		0-0	22-11-51	D43211P	A09			D42361P	A09			ALL

WIRE LIST

D280A108

91-21-11

Section W5460

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To										
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W5461	286A5461	FLIGHT RECORDER E3-2 SHELF TO E1-1 AND E5-2 SHELF (continued)												
2209Z		PA	0-0	22-11-51	D43211P	PERG	1F		D42361P	PERG	1F		ALL	
2210B	24	Y2 PB	22-11	22-11-51	D43211P	B17			D42361P	B10			YC051-YC055	
2210B	24	Y2 PB	23-6	22-11-51	D43211P	B17			D42361P	B10			YC056-YN235	
2210B	24	Y2 PB	23-5	22-11-51	D43211P	B17			D42361P	B10			YN236-YR328	
2210R	24	Y2 PB	0-0	22-11-51	D43211P	A17			D42361P	A10			ALL	
2210Z		PB	0-0	22-11-51	D43211P	PERG	1F		D42361P	PERG	1F		ALL	
2501B	22	PB QW	23-1	31-31-14	D42311P	A01			D42261P	A08			YC051-YC055	
2501B	22	PB QW	23-8	31-31-14	D42311P	A01			D42261P	A08			YC056-YN235	
2501B	22	PB QW	23-7	31-31-14	D42311P	A01			D42261P	A08			YN236-YR328	
2501R	22	PB QW	0-0	31-31-14	D42311P	A02			D42261P	A09			ALL	
2502B	22	PB QX	23-1	31-31-14	D42311P	A03			D42261P	B08			YC051-YC055	
2502B	22	PB QX	23-8	31-31-14	D42311P	A03			D42261P	B08			YC056-YN235	
2502B	22	PB QX	23-7	31-31-14	D42311P	A03			D42261P	B08			YN236-YR328	
2502R	22	PB QX	0-0	31-31-14	D42311P	A04			D42261P	B09			ALL	
2703B	24	Y2 MV	10-1	27-32-12	D44161P	B02			D42361P	A15			YC051-YC055	
2703B	24	Y2 MV	11-0	27-32-12	D44161P	B02			D42361P	A15			YC056-YD157	
2703R	24	Y2 MV	0-0	27-32-12	D44161P	A02			D42361P	A13			YC051-YD157	
2703Z		MV	0-0	27-32-12	D44161P	PERG	1F		D42361P	PERG	1F		YC051-YD157	
3001B	22	PC RA	32-10	27-32-11	D45261J	B04			D43261P	A16			YC051-YC055	
3001B	22	PC RA	33-5	27-32-11	D45261J	B04			D43261P	A16			YC056-YR328	
3001R	22	PC RA	0-0	27-32-11	D45261J	B03			D43261P	A15			ALL	
3001Y	22	PC RA	0-0	27-32-11	D45261J	B05			D43261P	A17			ALL	
3708B	22	PC JY	23-1	31-31-14	D42261P	A17			D42311P	B02			YC051-YC055	
3708B	22	PC JY	23-8	31-31-14	D42261P	A17			D42311P	B02			YC056-YN235	
3708B	22	PC JY	23-7	31-31-14	D42261P	A17			D42311P	B02			YN236-YR328	
3708R	22	PC JY	0-0	31-31-14	D42261P	A16			D42311P	B01			ALL	
3708Y	22	PC JY	0-0	31-31-14	D42261P	A18			D42311P	B03			ALL	
3709B	22	PC KY	23-1	31-31-14	D42261P	B17			D42311P	B05			YC051-YC055	
3709B	22	PC KY	23-8	31-31-14	D42261P	B17			D42311P	B05			YC056-YN235	
3709B	22	PC KY	23-7	31-31-14	D42261P	B17			D42311P	B05			YN236-YR328	
3709R	22	PC KY	0-0	31-31-14	D42261P	B16			D42311P	B04			ALL	
3709Y	22	PC KY	0-0	31-31-14	D42261P	B18			D42311P	B06			ALL	
W5463	286A5463	FLIGHT RECORDER E3-2 SHELF TO E/E BAY SHELF												
0001	22	PA	7-1	34-21-21	D41463J	43			D45263J	A10			ALL	
0003	24	B6	24-4	31-31-15	D42363P	A02			D41163P	A06			YC051-YC055	
0003	24	B6	24-5	31-31-15	D42363P	A02			D41163P	A06			YC056-YR328	
0004	24	B6	24-4	31-31-15	D42363P	B02			D41163P	B06			YC051-YC055	
0004	24	B6	24-5	31-31-15	D42363P	B02			D41163P	B06			YC056-YR328	

WIRE LIST

D280A108

91-21-11

Section W5460

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5463		286A5463			FLIGHT RECORDER E3-2 SHELF TO E/E BAY SHELF (continued)											
0005		24		PK		25-0	31-31-15	D43263P		A10		D41163P		A05		YC051-YC055
0005		24		PK		25-2	31-31-15	D43263P		A10		D41163P		A05		YC056-YR328
0008		22		PA		8-6	22-31-51	D41463J		2		D41163P		A08		ALL
0009		22		PA		8-6	22-31-51	D41463J		5		D41163P		B09		ALL
0010		22		PA		8-6	SPARE	D41463J		3		D41163P		A09		YC051-YD158
0010		22		PA		8-6	34-51-41	D41463J		3		D41163P		A09		YD160-YR328
0014		22		PA		8-6	22-31-51	D41463J		4		D41163P		B08		ALL
0015		20		PA		8-6	SPARE	D41163P		B15		D41463J		15		YC051-YD155
0016		22		PA		8-6	34-51-41	D41163P		B16		D41463J		16		ALL
0017		22		PA		8-6	34-51-41	D41163P		B17		D41463J		17		ALL
0020		22		PA		8-6	22-31-11	D41163P		B14		D41463J		36		YC051-YD155
0020		22		PA		8-6	SPARE	D41163P		B14		D41463J		36		YD157-YR328
0021		24		PK		24-4	21-51-24	D42363P		A01		D41163P		B07		YC051-YC055
0021		24		PK		24-5	21-51-24	D42363P		A01		D41163P		B07		YC056-YR328
0022		22		PA		7-1	SPARE	D45263J		A05		D41463J		14		ALL
0023		22		CQ		7-1	22-13-11	D45263J		A11		D41463J		37		ALL
0030		24		PK		23-5	SPARE	D42363P		A03		D41463J		44		YC051-YC055
0030		24		PK		23-6	SPARE	D42363P		A03		D41463J		44		YC056-YR328
0031		24		PK		23-5	SPARE	D42363P		B03		D41463J		45		YC051-YC055
0031		24		PK		23-6	SPARE	D42363P		B03		D41463J		45		YC056-YR328
0033		22		PA		8-6	34-51-41	D41163P		B13		D41463J		13		ALL
0034		24		B6		8-6	22-11-75	D41163P		A11		D41463J		18		ALL
0035		24		B6		8-6	22-11-75	D41163P		A12		D41463J		19		ALL
0036		24		B6		8-6	22-11-75	D41163P		A13		D41463J		20		ALL
0037		24		B6		8-6	22-11-75	D41163P		A14		D41463J		21		ALL
0038		24		B6		8-6	22-11-75	D41163P		A15		D41463J		22		ALL
0039		24		B6		8-6	22-11-75	D41163P		A16		D41463J		23		ALL
0040		24		B6		8-6	22-11-75	D41163P		A17		D41463J		24		ALL
0041		24		B6		8-6	22-11-75	D41163P		A18		D41463J		25		ALL
0042		24		B6		8-6	22-11-75	D41163P		A19		D41463J		26		ALL
0043		24		B6		8-6	22-11-75	D41163P		A20		D41463J		27		ALL
0044		24		B6		8-6	22-11-75	D41163P		B01		D41463J		28		ALL
0045		24		B6		8-6	22-11-75	D41163P		B11		D41463J		29		ALL
0046		24		B6		8-6	SPARE	D41163P		B12		D41463J		30		ALL
0047		24		B6		8-6	22-11-75	D41163P		B18		D41463J		31		ALL
0048		24		B6		8-6	22-11-75	D41163P		B19		D41463J		32		ALL
0049		24		B6		8-6	22-11-75	D41163P		B20		D41463J		33		ALL
0050		20		CQ		23-5	31-52-11	D41463J		1		D42363P		A06		YC051-YC055
0050		20		CQ		23-6	31-52-11	D41463J		1		D42363P		A06		YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W5460

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W5463	286A5463				FLIGHT RECORDER E3-2 SHELF TO E/E BAY SHELF (continued)											
0051	24		PK		25-2	27-28-11		D41563P	A08			D43263P	A18			ALL
0052	24		PK		25-2	27-28-11		D41563P	A09			D43263P	A19			ALL
0054	20		PA		25-2	27-25-11		D41563P	A02			D43263P	CAP	Y		YC051-YD155
0054	20		PA		25-2	SPARE		D41563P	A02			D43263P	A11			YD157
0055	20		PA		25-2	SPARE		D41563P	A03			D43263P	A13			YC051-YC055
0055	20		PA		25-4	SPARE		D41563P	A03			D43263P	A13			YC056-YL959, YN231-YN235
0061	24		B6		12-10	22-11-75		D45515P	A01			D45517J	1			YD157-YR328
0062	24		B6		12-10	22-11-75		D45515P	A02			D45517J	2			YD157-YR328
0063	24		B6		12-10	22-11-75		D45515P	A03			D45517J	3			YD157-YR328
0064	24		B6		12-10	22-11-75		D45515P	A04			D45517J	4			YD157-YR328
0065	24		B6		12-10	22-11-75		D45515P	A05			D45517J	5			YD157-YR328
0066	24		B6		12-10	22-11-75		D45515P	A06			D45517J	6			YD157-YR328
0067	24		B6		12-10	22-11-75		D45515P	A07			D45517J	7			YD157-YR328
0068	24		B6		12-10	22-11-75		D45515P	A08			D45517J	8			YD157-YR328
0069	24		B6		12-10	22-11-75		D45515P	A09			D45517J	9			YD157-YR328
0070	24		B6		12-10	22-11-75		D45515P	A10			D45517J	10			YD157-YR328
0071	24		B6		12-10	22-11-75		D45515P	A11			D45517J	11			YD157-YR328
0072	24		B6		12-10	22-11-75		D45515P	A12			D45517J	12			YD157-YR328
0073	24		B6		12-10	22-11-75		D45515P	B01			D45517J	13			YD157-YR328
0074	24		B6		12-10	22-11-75		D45515P	B02			D45517J	14			YD157-YR328
0075	24		B6		12-10	22-11-75		D45515P	B03			D45517J	15			YD157-YR328
0076	24		B6		12-7	22-11-75		D45515P	B04			D41463J	48			YD157-YR328
0077	24		B6		12-7	22-11-75		D45515P	B05			D41463J	49			YD157-YR328
0078	24		B6		12-7	22-11-75		D45515P	B06			D41463J	50			YD157-YR328
0079	24		B6		8-6	22-11-75		D41163P	B15			D41463J	38			YD157-YR328
0080	24		B6		12-7	22-11-75		D45515P	B07			D41463J	51			YD157-YR328
0200	24		B6		25-4	21-51-21		D41563P	A02			D43263P	A11			YD158-YR328
2002B	22		PB	JB	25-7	27-32-21		D43263P	B17			D45263J	B17			YC051-YC055
2002B	22		PB	JB	25-9	27-32-21		D43263P	B17			D45263J	B17			YC056-YR328
2002R	22		PB	JB	0-0	27-32-21		D43263P	A17			D45263J	A17			ALL
2003B	24		Y2	JC	25-0	27-32-22		D43263P	B05			D41163P	B04			YC051-YC055
2003B	24		Y2	JC	25-2	27-32-22		D43263P	B05			D41163P	B04			YC056-YR328
2003R	24		Y2	JC	0-0	27-32-22		D43263P	A05			D41163P	A04			ALL
2003Z				JC	0-0	27-32-22		D43263P	PERG	1F		D41163P	PERG	1F		ALL
2004B	24		Y2	JD	8-6	22-31-52		D41163P	B10			D41463J	7			ALL
2004R	24		Y2	JD	0-0	22-31-52		D41163P	A10			D41463J	6			ALL
2004Z				JD	0-0	22-31-52		D41163P	PERG	1F		D41463J	S/R			ALL
2005B	24		Y2	JE	24-4	34-33-21		D41163P	B02			D42363P	B04			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5460

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5463 286A5463 FLIGHT RECORDER E3-2 SHELF TO E/E BAY SHELF (continued)																
2005B	24	Y2		JE		24-5	34-33-21	D41163P	B02			D42363P	B04			YC056-YR328
2005R	24	Y2		JE		0-0	34-33-21	D41163P	A02			D42363P	A04			ALL
2005Z				JE		0-0	34-33-21	D41163P	PERG	1F		D42363P	PERG	1F		ALL
2006B	24	Y2		JF		24-4	34-33-21	D41163P	B03			D42363P	B05			YC051-YC055
2006B	24	Y2		JF		24-5	34-33-21	D41163P	B03			D42363P	B05			YC056-YR328
2006R	24	Y2		JF		0-0	34-33-21	D41163P	A03			D42363P	A05			ALL
2006Z				JF		0-0	34-33-21	D41163P	PERG	1F		D42363P	PERG	1F		ALL
2007B	24	Y2		JG		24-11	31-35-02	D42363P	A08			D45263J	B02			YC051-YC055
2007B	24	Y2		JG		25-0	31-35-02	D42363P	A08			D45263J	B02			YC056-YR328
2007R	24	Y2		JG		0-0	31-35-02	D42363P	A07			D45263J	B01			ALL
2007Z				JG		0-0	31-35-02	D42363P	PERG	1F		D45263J	PERG	1F		ALL
2009B	24	Y2		JI		24-2	27-32-22	D43263P	B12			D41463J	9			YC051-YC055
2009B	24	Y2		JI		24-3	27-32-22	D43263P	B12			D41463J	9			YC056-YR328
2009R	24	Y2		JI		0-0	27-32-22	D43263P	A12			D41463J	8			ALL
2009Z				JI		0-0	27-32-22	D43263P	PERG	1F		D41463J	S/R			ALL
2010B	24	Y2		AB		25-7	34-21-24	D43263P	B06			D45263J	B06			YC051-YC055
2010B	24	Y2		AB		25-9	34-21-24	D43263P	B06			D45263J	B06			YC056-YD157
2010R	24	Y2		AB		0-0	34-21-24	D43263P	A06			D45263J	A06			YC051-YD157
2010Z				AB		0-0	34-21-24	D43263P	PERG	1F		D45263J	PERG	1F		YC051-YD157
2011B	24	Y2		JJ		25-7	34-61-24	D43263P	B03			D45263J	B03			YC051-YC055
2011B	24	Y2		JJ		25-9	34-61-24	D43263P	B03			D45263J	B03			YC056-YR328
2011R	24	Y2		JJ		0-0	34-61-24	D43263P	A03			D45263J	A03			ALL
2011Z				JJ		0-0	34-61-24	D43263P	PERG	1F		D45263J	PERG	1F		ALL
2012B	24	Y2		JK		25-7	34-61-14	D43263P	B04			D45263J	B04			YC051-YC055
2012B	24	Y2		JK		25-9	34-61-14	D43263P	B04			D45263J	B04			YC056-YR328
2012R	24	Y2		JK		0-0	34-61-14	D43263P	A04			D45263J	A04			ALL
2012Z				JK		0-0	34-61-14	D43263P	PERG	1F		D45263J	PERG	1F		ALL
2013B	22	X2		JL		25-7	SPARE	D43263P	B07			D45263J	B07			YC051-YC055
2013B	22	X2		JL		25-9	SPARE	D43263P	B07			D45263J	B07			YC056-YD157
2013B	24	Y2		JL		25-9	SPARE	D43263P	B07			D45263J	B07			YD158-YR328
2013R	22	X2		JL		0-0	SPARE	D43263P	A07			D45263J	A07			YC051-YD157
2013R	24	Y2		JL		0-0	SPARE	D43263P	A07			D45263J	A07			YD158-YR328
2013Z				JL		0-0	SPARE	D43263P	PERG	1F		D45263J	PERG	1F		ALL
2014B	22	X2		JM		25-0	SPARE	D43263P	A08			D41163P	A07			YC051-YC055
2014B	22	X2		JM		25-2	SPARE	D43263P	A08			D41163P	A07			YC056-YD157
2014B	24	Y2		JM		25-9	SPARE	D43263P	B08			D45263J	B08			YD158-YR328
2014R	22	X2		JM		0-0	SPARE	D43263P	B08			D41163P	B05			YC051-YD157
2014R	24	Y2		JM		0-0	SPARE	D43263P	A08			D45263J	A08			YD158-YR328
2014Z				JM		0-0	SPARE	D43263P	PERG	1F		D41163P	PERG	1F		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W5460

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W5463	286A5463	FLIGHT RECORDER E3-2 SHELF TO E/E BAY SHELF (continued)			
2014Z		JM	0-0 SPARE D43263P	PERG 1F D45263J	YD158-YR328
2015B	24	Y2 JN	25-7 34-21-24 D43263P	B09 D45263J	YC051-YC055
2015B	24	Y2 JN	25-9 34-21-24 D43263P	B09 D45263J	YC056-YR328
2015R	24	Y2 JN	0-0 34-21-24 D43263P	A09 D45263J	ALL
2015Z		JN	0-0 34-21-24 D43263P	PERG 1F D45263J	ALL
2016B	24	Y2 JO	25-7 34-21-23 D43263P	B16 D45263J	YC051-YC055
2016B	24	Y2 JO	25-9 34-21-23 D43263P	B16 D45263J	YC056-YR328
2016R	24	Y2 JO	0-0 34-21-23 D43263P	A16 D45263J	ALL
2016Z		JO	0-0 34-21-23 D43263P	PERG 1F D45263J	ALL
2017B	24	Y2 JP	25-7 34-21-23 D43263P	B15 D45263J	YC051-YC055
2017B	24	Y2 JP	25-9 34-21-23 D43263P	B15 D45263J	YC056-YR328
2017R	24	Y2 JP	0-0 34-21-23 D43263P	A15 D45263J	ALL
2017Z		JP	0-0 34-21-23 D43263P	PERG 1F D45263J	ALL
2018B	24	Y2 JQ	7-1 34-61-14 D41463J	11 D45263J	ALL
2018R	24	Y2 JQ	0-0 34-61-14 D41463J	10 D45263J	ALL
2018Z		JQ	0-0 34-61-14 D41463J	S/R D45263J	ALL
2019B	24	Y2 JW	25-7 SPARE D43263P	B14 D45263J	YC051-YC055
2019B	24	Y2 JW	25-9 SPARE D43263P	B14 D45263J	YC056-YL959, YN231-YN235
2019R	24	Y2 JW	0-0 SPARE D43263P	A14 D45263J	YC051-YL959, YN231-YN235
2019Z		JW	0-0 SPARE D43263P	PERG 1F D45263J	YC051-YL959, YN231-YN235
2021B	24	PL JU	25-2 27-28-11 D41563P	B01 D43263P	ALL
2021R	24	PL JU	0-0 27-28-11 D41563P	A10 D43263P	ALL
2022B	24	Y2 JV	24-11 SPARE D42363P	A10 D45263J	YC051-YC055
2022B	24	Y2 JV	25-0 SPARE D42363P	A10 D45263J	YC056-YR328
2022R	24	Y2 JV	0-0 SPARE D42363P	A09 D45263J	ALL
2022Z		JV	0-0 SPARE D42363P	PERG 1F D45263J	ALL
2023B	24	Y2 JX	24-6 22-23-12 D42363P	B07 D41563P	YC051-YC055
2023B	24	Y2 JX	24-7 22-23-12 D42363P	B07 D41563P	YC056-YR328
2023R	24	Y2 JX	0-0 22-23-12 D42363P	B06 D41563P	ALL
2023Z		JX	0-0 22-23-12 D42363P	PERG 1F D41563P	ALL
2035B	24	Y2 AE	24-11 31-33-01 D42363P	B09 D45263J	YC051-YC055
2035B	24	Y2 AE	25-0 31-33-01 D42363P	B09 D45263J	YC056-YD157
2035B	24	Y2 KJ	25-0 31-33-01 D42363P	B09 D45263J	YD158-YR328
2035R	24	Y2 AE	0-0 31-33-01 D42363P	B08 D45263J	YC051-YD157
2035R	24	Y2 KJ	0-0 31-33-01 D42363P	B08 D45263J	YD158-YR328
2035Z		AE	0-0 31-33-01 D42363P	PERG 1F D45263J	YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W5460

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity

W5463		286A5463		FLIGHT RECORDER E3-2 SHELF TO E/E BAY SHELF (continued)											
2035Z				KJ	0-0	31-33-01	D42363P	PERG	1F		D45263J	PERG	1F		YD158-YR328
3001B	22	PC	AD		25-7	27-32-21	D43263P		B19		D45263J		B19		YC051-YC055
3001B	22	PC	AD		25-9	27-32-21	D43263P		B19		D45263J		B19		YC056-YR328
3001R	22	PC	AD		0-0	27-32-21	D43263P		B18		D45263J		B18		ALL
3001Y	22	PC	AD		0-0	27-32-21	D43263P		B20		D45263J		B20		ALL

WIRE LIST

D280A108

91-21-11

Section W5460

Page 14 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5501	286A5501				ADIRU NO.1 TO AOA-L,ADM-L PITOT, AND TAT PROBE										
0001	20		PA		3-8	34-21-12	D03689		18		GD00433	DC..	E		ALL
0002	22		PA		0-7	34-21-12	D03689		14		D03689	17			ALL
0003	20		PA		3-4	34-21-12	D00277		7		GD00171	DC..	E		ALL
0004	20		PA		3-4	34-21-12	D00277		6		GD00171	DC..	E		ALL
0005	22		PA		28-0	34-21-12	D10015		1		D45239J	B01			ALL
0006	20		PA		4-4	34-21-12	D10015		2		GD00602	AC..	E		ALL
0007	20		PA		3-0	34-21-12	D10015		12		GD00433	DC..	E		ALL
0008	22		CQ		5-4	30-31-11	D00277		1		D40087P	A04			ALL
0009	22		PA		4-3	27-32-11	D00365		10		GD00602	AC..	E		ALL
0010	22		PA		3-9	27-32-11	D00365		12		GD00435	ST..	E		ALL
0011	22		CQ		12-11	30-31-11	D00365		8		D40087P	A05			ALL
0012	22		CQ		12-11	30-31-11	D00365		9		D40087P	A06			ALL
0013	22		CQ		3-1	30-31-11	D11294		=B		GD00602	AC..	E		ALL
0014	22		CQ		14-5	30-31-11	D11294		=A		D40087P	A03			ALL
2001B	22		PB	EA	27-11	27-32-11	D00365		2		D45239J	B05			ALL
2001R	22		PB	EA	0-0	27-32-11	D00365		1		D45239J	B04			ALL
2501B	24		Y2	FA	27-6	34-21-12	D03689		8		D45239J	A02			ALL
2501R	24		Y2	FA	0-0	34-21-12	D03689		7		D45239J	A01			ALL
2501Z				FA	0-0	34-21-12	D03689	PERB			D45239J	PERG	1F		ALL
2502B	20		X2	FB	19-5	34-21-12	D00277		4		D45239J	A07			ALL
2502R	20		X2	FB	0-0	34-21-12	D00277		3		D45239J	A06			ALL
2502Z				FB	0-0	34-21-12	D00277	DED			D45239J	PERG	1F		ALL
2503B	24		Y2	FC	19-5	34-21-22	D00277		2		D45239J	B03			ALL
2503R	24		Y2	FC	0-0	34-21-22	D00277		5		D45239J	B02			ALL
2503Z				FC	0-0	34-21-22	D00277	DED			D45239J	PERG	1F		ALL
2504B	22		X2	FD	22-0	34-61-14	D45239J	B10			D40087P	B02			ALL
2504R	22		X2	FD	0-0	34-61-14	D45239J	B09			D40087P	B01			ALL
2504Z				FD	0-0	34-61-14	D45239J	PERG	1F		D40087P	PERG	1F		ALL
2505B	22		X2	FE	22-0	28-41-11	D45239J	B12			D40087P	A02			ALL
2505R	22		X2	FE	0-0	28-41-11	D45239J	B11			D40087P	A01			ALL
2505Z				FE	0-0	28-41-11	D45239J	PERG	1F		D40087P	PERG	1F		ALL
2506B	24		Y2	AF	22-0	34-21-13	D45239J	A12			D40087P	A08			YC051-YC052
2506R	24		Y2	AF	0-0	34-21-13	D45239J	A11			D40087P	A07			YC051-YC052
2506Z				AF	0-0	34-21-13	D45239J	PERG	1F		D40087P	PERG	1F		YC051-YC052
2507B	24		Y2	AG	22-0	34-21-14	D45239J	A14			D40087P	A10			YC051-YC052
2507R	24		Y2	AG	0-0	34-21-14	D45239J	A13			D40087P	A09			YC051-YC052
2507Z				AG	0-0	34-21-14	D45239J	PERG	1F		D40087P	PERG	1F		YC051-YC052
3001B	24		PM	GA	28-0	34-21-12	D10015		4		D45239J	A09			ALL
3001R	24		PM	GA	0-0	34-21-12	D10015		3		D45239J	A08			ALL

WIRE LIST

D280A108

91-21-11

Section W5500

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From	To			Effectivity				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5501	286A5501			ADIRU NO.1 TO AOA-L,ADM-L PITOT, AND TAT PROBE (continued)											
3001Y	24	PM	GA		0-0	34-21-12	D10015	5			D45239J	A10			ALL
3002B	22	PC	GB		27-11	27-32-11	D00365	4			D45239J	B07			ALL
3002R	22	PC	GB		0-0	27-32-11	D00365	3			D45239J	B06			ALL
3002Y	22	PC	GB		0-0	27-32-11	D00365	5			D45239J	B08			ALL
3501B	22	X3	HA		27-6	34-21-12	D03689	3			D45239J	A04			ALL
3501R	22	X3	HA		0-0	34-21-12	D03689	1			D45239J	A03			ALL
3501Y	22	X3	HA		0-0	34-21-12	D03689	5			D45239J	A05			ALL
3501Z			HA		0-0	34-21-12	D03689	PERB			D45239J	PERG	1F		ALL
W5502	286A5502			LEFT A/C PACK (STA 536L) DISC TO A/C PACK (SA2)											
0001	20		HA		3-5	33-33-11	D41500	15			L00182	=P	BK		YC051-YL999, YR301-YR328
0001	20		HA		3-6	33-33-11	D41500	15			L00182	=P	BK		YN231-YN501
0002	20		HA		9-0	33-33-11	D41500	16			L00183	=P	BK		YC051-YL999, YR301-YR328
0002	20		HA		8-4	33-33-11	D41500	16			L00183	=P	BK		YN231-YN501
0003	20		HA		2-0	33-33-11	L00182	=G	G7		GD05520	AC..	GW	*1	YC051-YL999, YR301-YR328
0003	20		HA		1-6	33-33-11	L00182	=G	G7		GD00554	AC..	GW		YN231-YN501
0004	20		HA		6-3	33-33-11	L00183	=G	G7		GD05520	AC..	GW	*1	YC051-YD152
0004	20		HA		6-2	33-33-11	L00183	=G	G7		GD05520	AC..	GW	*1	YD153-YL999, YR301-YR328
0004	20		HA		6-7	33-33-11	L00183	=G	G7		GD00554	AC..	GW		YN231-YN501
0005	20		HA		2-0	34-61-17	D00398	7			GD03250	DC..	GW		YC051-YL999, YR301-YR328
0005	20		HA		1-11	34-61-17	D00398	7			GD03250	DC..	GW		YN231-YN501
0006	20		HA		1-5	21-61-11	D03886	13			GD02324	ST..	GW		YC051-YL999, YR301-YR328
1001	20		HE	AA	6-9	21-42-11	D00486	2			D41500	8			YC051-YD152
1001Z				AA	0-0	21-42-11	GD02328	ST..	GW	*1	D41500	S/R			YC051-YD152
1002	20		HE	AB	6-6	21-51-11	D00962	1			D41500	3			YC051-YD152
1002	20		HE	AB	6-7	21-51-11	D00962	1			D41500	3			YD153-YL999, YR301-YR328
1002	20		HE	AB	5-2	21-51-11	D00962	1			D41500	3			YN231-YN501
1002Z				AB	0-0	21-51-11	GD02328	ST..	GW	*1	D41500			AA	YC051-YD152
1002Z				AB	0-0	21-51-11	GD02328	ST..	GW	*2	D41500			AA	YD153
1002Z				AB	0-0	21-51-11	GD02328	ST..	GW	*2	D41500	S/R		*1	YD154-YR328
1003	20		HE	AC	6-9	21-51-11	D00486	3			D41500	4			YC051-YD152
1003Z				AC	0-0	21-51-11	GD02328	ST..	GW	*2	D41500			AA	YC051-YD152

WIRE LIST

D280A108

91-21-11

Section W5500

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description			From			To							
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5502	286A5502	LEFT A/C PACK (STA 536L) DISC TO A/C PACK (SA2) (continued)													
1004	20	HE	AD		2-10	21-51-11	D00962	2			GD05524	DC..	GW	*1	YC051-YD152
1004	20	HE	AD		3-7	21-51-11	D00962	2			GD05524	DC..	GW	*1	YD153-YL999, YR301-YR328
1004	20	HE	AD		3-7	21-51-11	D00962	2			GD00390	DC..	GW	*3	YN231-YN501
1004Z			AD		0-0	21-51-11	GD02328	ST..	GW	*1	GD05524	DC..	GW	*1	YC051-YD152
1004Z			AD		0-0	21-51-11	GD02328	ST..	GW	*2	GD05524	DC..	GW	*1	YD153-YL999, YR301-YR328
1004Z			AD		0-0	21-51-11	GD02328	ST..	GW	*3	GD00390	DC..	GW	*3	YN231-YN501
1005	20	HE	AE		3-1	21-51-11	D00486	1			GD05524	DC..	GW	*2	YC051-YD152
1005Z			AE		0-0	21-51-11	GD02328	ST..	GW	*3	GD05524	DC..	GW	*2	YC051-YD152
1006	20	HE	AF		2-1	21-51-11	D00488	3			GD05524	DC..	GW	*3	YC051-YD152
1006	20	HE	AF		2-9	21-51-11	D00488	3			GD05524	DC..	GW	*3	YD153-YL999, YR301-YR328
1006	20	HE	AF		3-3	21-51-11	D00488	3			GD00390	DC..	GW	*1	YN231-YN501
1006Z			AF		0-0	21-51-11	GD02328	ST..	GW	*2	GD05524	DC..	GW	*3	YC051-YD152
1006Z			AF		0-0	21-51-11	GD02328	ST..	GW		GD05524	DC..	GW	*3	YD153-YL999, YR301-YR328
1006Z			AF		0-0	21-51-11	GD02328	ST..	GW	*3	GD00390	DC..	GW	*1	YN231-YN501
1007	20	HE	AG		7-6	36-11-11	D00398	3			GD00548	AC..	GW	*1	YC051-YL999, YR301-YR328
1007	20	HE	AG		7-3	36-11-11	D00398	3			GD00548	AC..	GW	*1	YN231-YN501
1007Z			AG		0-0	36-11-11	GD03250	DC..	GW	*1	GD00548	AC..	GW	*1	ALL
1008	20	HE	AH		3-2	34-61-17	D41500	13			D00398	6			ALL
1008Z			AH		0-0	34-61-17	D41500	S/R			GD03250	DC..	GW	*1	YC051-YL999, YR301-YR328
1008Z			AH		0-0	34-61-17	D41500	S/R			GD03250	DC..	GW		YN231-YN501
1010R	20	H9	AJ		5-2	26-12-11	M01909	=A	GW		D00856	=1			YC051-YD152
1010R	20	H9	AJ		5-1	26-12-11	M01909	=A	GW		D00856	=1			YD153-YL999, YR301-YR328
1010R	20	H9	AJ		4-1	26-12-11	M01909	=A	GW		D00856	=1			YN231-YN501
1010Z			AJ		0-0	26-12-11	GD02326	ST..	GW		GD02330	ST..	GW	*1	ALL
1011R	20	H9	AK		8-0	26-12-11	D41500	14			M01909	=B	GW		YC051-YL999, YR301-YR328
1011R	20	H9	AK		7-4	26-12-11	D41500	14			M01909	=B	GW		YN231-YN501
1011Z			AK		0-0	26-12-11	D41500	S/R			GD02330	ST..	GW	*1	ALL
1016	20	HE	AQ		2-7	21-51-11	D40844P	1			GD05524	DC..	GW	*2	YD153-YD157
1016	20	HE	AQ		3-0	21-51-11	D40844P	1			GD05524	DC..	GW	*2	YD158-YL999, YR301-YR328
1016	20	HE	AQ		3-0	21-51-11	D40844P	1			GD00390	DC..	GW	*2	YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W5500

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description			From			To			Effectivity				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5502	286A5502	LEFT A/C PACK (STA 536L) DISC TO A/C PACK (SA2) (continued)													
1016Z				AQ	0-0	21-51-11	D40844P	S/R			GD05524	DC..	GW	*2	YD153-YL999, YR301-YR328
1016Z				AQ	0-0	21-51-11	D40844P	S/R			GD00390	DC..	GW	*2	YN231-YN501
1017	20	HE	AR		5-2	21-42-11	D40844P	2			D41500	8			YD153-YD157
1017	20	HE	AR		4-11	21-42-11	D40844P	2			D41500	8			YD158-YL999, YR301-YR328
1017	20	HE	AR		4-8	21-42-11	D40844P	2			D41500	8			YN231-YN501
1017Z				AR	0-0	21-42-11	D40844P	S/R			D41500	S/R			YD153-YR328
1018	20	HE	AS		5-2	21-51-11	D40844P	3			D41500	4			YD153-YD157
1018	20	HE	AS		4-11	21-51-11	D40844P	3			D41500	4			YD158-YL999, YR301-YR328
1018	20	HE	AS		4-8	21-51-11	D40844P	3			D41500	4			YN231-YN501
1018Z				AS	0-0	21-51-11	D40844P	S/R			D41500			AA	YD153
1018Z				AS	0-0	21-51-11	D40844P	S/R			D41500	S/R		*2	YD154-YR328
1035	20	HE	BJ		3-9	21-61-11	D03886	3			GD05520	AC..	GW	*2	YC051-YL999, YR301-YR328
1035Z				BJ	0-0	21-61-11	D03886			AB	GD05520	AC..	GW	*2	YC051-YD153
1035Z				BJ	0-0	21-61-11	GD02324	ST..	GW	*	GD05520	AC..	GW	*2	YD154-YL999, YR301-YR328
1037	20	HE	BL		2-10	21-61-11	D41500	19			D03886	10			YC051-YL999, YR301-YR328
1037Z				BL	0-0	21-61-11	D41500	S/R			D03886			AB	YC051-YD153
1037Z				BL	0-0	21-61-11	D41500	S/R			GD02324	ST..	GW	*	YD154-YL999, YR301-YR328
1038	20	HE	BM		2-0	21-61-11	D03886	5			GD03250	DC..	GW	*2	YC051-YL999, YR301-YR328
1038Z				BM	0-0	21-61-11	D03886			AB	GD03250	DC..	GW	*2	YC051-YD153
1038Z				BM	0-0	21-61-11	GD02324	ST..	GW	*	GD03250	DC..	GW	*2	YD154-YL999, YR301-YR328
1039	20	HE	BN		2-10	21-61-11	D41500	20			D03886	11			YC051-YL999, YR301-YR328
1039Z				BN	0-0	21-61-11	D41500	S/R			D03886			AB	YC051-YD153
1039Z				BN	0-0	21-61-11	D41500	S/R			GD02324	ST..	GW	*	YD154-YL999, YR301-YR328
2001B	20	HF	GA		5-1	21-51-11	D00392	1			D41500	1			YC051-YD152
2001B	20	HF	GA		5-0	21-51-11	D00392	1			D41500	1			YD153-YL999, YR301-YR328
2001B	20	HF	GA		4-10	21-51-11	D00392	1			D41500	1			YN231-YN501
2001R	20	HF	GA		0-0	21-51-11	D00392	2			D41500	2			ALL

WIRE LIST

D280A108

91-21-11

Section W5500

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W5502	286A5502	LEFT A/C PACK (STA 536L) DISC TO A/C PACK (SA2) (continued)													
2001Z		GA	0-0	21-51-11	GD05526	ST..	GW		D41500			AA	YC051-YD153		
2001Z		GA	0-0	21-51-11	GD05526	ST..	GW		D41500	S/R		*1	YD154-YL999, YR301-YR328		
2001Z		GA	0-0	21-51-11	GD02328	ST..	GW	*2	D41500	S/R		*1	YN231-YN501		
2002B	20	HF	5-4	21-51-11	D00488	1			D41500	5			YC051-YL999, YR301-YR328		
2002B	20	HF	GB	4-10	21-51-11	D00488	1		D41500	5			YN231-YN501		
2002R	20	HF	GB	0-0	21-51-11	D00488	5		D41500	6			ALL		
2002Z		GB	0-0	21-51-11	GD02328	ST..	GW	*3	D41500			AA	YC051-YD152		
2002Z		GB	0-0	21-51-11	GD02328	ST..	GW	*2	D41500			AA	YD153		
2002Z		GB	0-0	21-51-11	GD02328	ST..	GW	*2	D41500	S/R		*2	YD154-YL999, YR301-YR328		
2002Z		GB	0-0	21-51-11	GD02328	ST..	GW	*3	D41500	S/R		*2	YN231-YN501		
2083B	20	HF	JH	2-10	21-61-11	D41500	17		D03886	1			YC051-YL999, YR301-YR328		
2083R	20	HF	JH	0-0	21-61-11	D41500	18		D03886	2			YC051-YL999, YR301-YR328		
2083Z		JH	0-0	21-61-11	D41500	S/R			D03886			AB	YC051-YD153		
2083Z		JH	0-0	21-61-11	D41500	S/R			GD02324	ST..	GW	*	YD154-YL999, YR301-YR328		
2084B	20	HF	JI	2-10	21-61-11	D41500	21		D03886	12			YC051-YL999, YR301-YR328		
2084R	20	HF	JI	0-0	21-61-11	D41500	22		D03886	4			YC051-YL999, YR301-YR328		
2084Z		JI	0-0	21-61-11	D41500	S/R			D03886			AB	YC051-YD153		
2084Z		JI	0-0	21-61-11	D41500	S/R			GD02324	ST..	GW	*	YD154-YL999, YR301-YR328		
4001B	20	HS	A6	3-2	36-11-11	D41500	9		D00398	2			ALL		
4001G	20	HS	A6	0-0	36-11-11	D41500	12		D00398	5			ALL		
4001R	20	HS	A6	0-0	36-11-11	D41500	10		D00398	1			ALL		
4001Y	20	HS	A6	0-0	36-11-11	D41500	11		D00398	4			ALL		
4001Z		A6	0-0	36-11-11	D41500	S/R			GD03250	DC..	GW	*1	ALL		
FRAA			0-0	21-51-11	D41500			AA	D41500	S/R			YC051-YD153		
FRAB			0-0	21-61-11	D03886			AB	GD02324	ST..	GW		YC051-YD153		
W5503	286A5503	ADIRU NO.2 TO AOA-R AND ADM-R PITOT													
0001	20	PA	1-6	34-21-22	D03695	18			GD01753	DC..	E		ALL		
0002	22	PA	0-7	34-21-22	D03695	14			D03695	17			ALL		
0003	22	CQ	13-5	30-31-12	D00287	8			D40097P	A02			ALL		

WIRE LIST

D280A108

91-21-11
Section W5500
Page 5
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5503		286A5503			ADIRU NO.2 TO AOA-R AND ADM-R PITOT (continued)											
0004		22		CQ		13-5	30-31-12	D00287		9		D40097P	A03			ALL
0005		22		PA		18-9	34-21-22	D10017		1		D45241J	B01			ALL
0006		20		PA		3-4	34-21-22	D10017		2		GD00606	AC..	E		ALL
0007		20		PA		2-10	34-21-22	D10017		12		GD00439	DC..	E		ALL
0008		22		PA		3-4	27-32-21	D00287		10		GD00606	AC..	E		ALL
0009		22		PA		2-9	27-32-21	D00287		12		GD00437	ST..	E		ALL
0010		22		CQ		14-10	30-31-12	D11300		= A		D40097P	A04			ALL
0011		22		CQ		3-2	30-31-12	D11300		= B		GD00606	AC..	E		ALL
0012		22		CQ		13-11	30-31-12	D11298		= A		D40097P	A01			ALL
0013		22		CQ		2-3	30-31-12	D11298		= B		GD00606	AC..	E		ALL
0017		20		CQ		15-5	21-33-11	D14284		A		D40097P	B09			YC060-YC064
0017		20		CQ		4-6	21-33-11	GD00802	DC..	1		D14284	B			YL952-YL999, YN232-YR328
0018		20		CQ		4-7	21-33-11	D14284		B		GD00802	DC..	1A		YC060-YC064
0018		22		CQ		15-4	21-33-11	D40097P		B09	VP	D14284	A			YL952, YN232
0018		22		CQ		15-4	21-33-11	D40097P		B09		D14284	A			YL953-YL999, YN233-YR328
2001B		22		PB	EA	18-9	27-32-21	D00287		2		D45241J	B03			ALL
2001R		22		PB	EA	0-0	27-32-21	D00287		1		D45241J	B02			ALL
2501B		24		Y2	FA	20-7	34-21-22	D03695		8		D45241J	A02			ALL
2501R		24		Y2	FA	0-0	34-21-22	D03695		7		D45241J	A01			ALL
2501Z					FA	0-0	34-21-22	D03695		PERB		D45241J	PERG	1F		ALL
2502B		24		Y2	AB	13-11	34-21-23	D45241J		B08		D40097P	A06			YC051-YC052
2502R		24		Y2	AB	0-0	34-21-23	D45241J		B07		D40097P	A05			YC051-YC052
2502Z					AB	0-0	34-21-23	D45241J		PERG	1F	D40097P	PERG	1F		YC051-YC052
2503B		24		Y2	AC	13-11	34-21-24	D45241J		A07		D40097P	A08			YC051-YC052
2503R		24		Y2	AC	0-0	34-21-24	D45241J		A06		D40097P	A07			YC051-YC052
2503Z					AC	0-0	34-21-24	D45241J		PERG	1F	D40097P	PERG	1F		YC051-YC052
3001B		24		PM	GA	18-9	34-21-22	D10017		3		D45241J	A09			ALL
3001R		24		PM	GA	0-0	34-21-22	D10017		4		D45241J	A08			ALL
3001Y		24		PM	GA	0-0	34-21-22	D10017		5		D45241J	A10			ALL
3002B		22		PC	GB	18-9	27-32-21	D00287		4		D45241J	B05			ALL
3002R		22		PC	GB	0-0	27-32-21	D00287		3		D45241J	B04			ALL
3002Y		22		PC	GB	0-0	27-32-21	D00287		5		D45241J	B06			ALL
3501B		22		X3	HA	20-7	34-21-22	D03695		3		D45241J	A04			ALL
3501R		22		X3	HA	0-0	34-21-22	D03695		1		D45241J	A03			ALL
3501Y		22		X3	HA	0-0	34-21-22	D03695		5		D45241J	A05			ALL
3501Z					HA	0-0	34-21-22	D03695		PERB		D45241J	PERG	1F		ALL

WIRE LIST

D280A108

91-21-11

Section W5500

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5504	286A5504			LEFT A/C PACK (STA 536L) DISC TO A/C PACK (SA2)											
1001	20	HE	AA		2-3	21-51-11	D00486		1		D40844J	1			YD153-YR328
1001Z			AA		0-0	21-51-11	D00486	DED			D40844J	S/R			YD153-YR328
1002	20	HE	AB		2-3	21-42-11	D00486		2		D40844J	2			YD153-YR328
1002Z			AB		0-0	21-42-11	D00486	DED			D40844J	S/R			YD153-YR328
1003	20	HE	AC		2-3	21-51-11	D00486		3		D40844J	3			YD153-YR328
1003Z			AC		0-0	21-51-11	D00486	DED			D40844J	S/R			YD153-YR328
W5506	286A5506			P8 TO E/E BAY											
0001	22	PA			19-11	35-21-11	D40802P		1		D40686P	12			YC051-YC055
0001	22	PA			20-1	35-21-11	D40802P		1		D40686P	12			YC056-YD158
0001	22	PA			20-3	35-21-11	D40802P		1		D40686P	12			YL951-YL968, YN231-YN236, YN501-YR328
0002	22	CQ			31-3	35-21-11	D40686P		13		D40806J	5			YC051-YC055
0002	22	CQ			31-4	35-21-11	D40686P		13		D40806J	5			YC056-YD158
0002	22	CQ			31-6	35-21-11	D40686P		13		D40806J	5			YL951-YL968, YN231-YN236, YN501-YR328
0003	18	CQ			27-2	33-25-11	D40686P		1		D40800P	21			YC051-YD158, YL951-YL952, YN231-YN236, YN501
0003	20	CQ			27-2	33-25-11	D40686P		1		D40800P	39			YL953-YL968, YR301-YR328
0004	18	CQ			27-2	33-25-11	D40686P		2		D40800P	23			YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0005	18	PA			18-9	33-42-11	TB1806V	A015	1		D40430P	1	18		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0011	22	PA			15-2	33-25-11	D40686P		4		SM00020		S		YC051-YC055
0011	22	PA			15-3	33-25-11	D40686P		4		SM00020		S		YC056-YD158
0011	22	PA			15-5	33-25-11	D40686P		4		SM00020		S		YL951-YL968, YN231-YN236, YN501-YR328
0012	22	PA			18-11	33-25-11	D40804P		1		SM00020		S		YC051-YC055

WIRE LIST

D280A108

91-21-11
Section W5500
Page 7
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5506	286A5506				P8 TO E/E BAY (continued)										
0012	22		PA		19-0	33-25-11	D40804P	1			SM00020		S		YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0013	22		PA		5-4	33-25-11	D40802P	2			SM00020		S		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0015	22		CQ		19-0	35-11-11	D40802P	8			D40806J	39			YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0019	10		CQ		14-1	30-42-11	SP01080		9		SP01082		9		YC062-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0039	22		PA		26-7	27-62-11	D43900P	1			D40800P	36			YL953-YL968
0039	22		PA		26-6	27-62-11	D43900P	1			D40800P	36			YR301-YR328
0040	22		PA		26-7	27-62-11	D43900P	7			D40800P	33			YL953-YL968
0040	22		PA		26-6	27-62-11	D43900P	7			D40800P	33			YR301-YR328
0041	22		PA		13-10	27-62-11	D44276	=1			D40800P	32			YL953-YL968
0041	22		PA		13-10	27-62-11	D44276	=1	VS		D40800P	32			YR301-YR314, YR318, YR320-YR328
0041	22		PA		13-10	27-62-11	D44276	=1	VY		D40800P	32			YR315-YR317, YR319
0042	22		PA		25-1	27-62-11	D43900P	3			D46128P	B08			YL953-YL968
0042	22		PA		24-11	27-62-11	D43900P	3			D46128P	B08			YR301-YR328
0043	22		PA		25-1	27-62-11	D43900P	4			D46128P	B07			YL953-YL968
0043	22		PA		24-11	27-62-11	D43900P	4			D46128P	B07			YR301-YR328
0044	22		PA		25-1	27-62-11	D43900P	6			D46128P	B09			YL953-YL968
0044	22		PA		24-11	27-62-11	D43900P	6			D46128P	B09			YR301-YR328
0074	16		CQ		19-0	47-30-11	D40802P	24	16		D40806J	16	16		YL951-YL968, YN231-YN236, YN501-YR328
0506	20		PA		11-11	29-11-11	D00576	25			D40800P	3			YC051-YC055
0506	20		PA		12-0	29-11-11	D00576	25			D40800P	3			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W5500

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Fam	Description FT-IN	Diagram	From Equip			Term	Type	Splice	To Equip			Term	Type	Splice	Effectivity
W5506	286A5506				P8 TO E/E BAY (continued)														
0507	20		PA		16-1	29-11-11	D00576		26				D40806J		3				YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0508	20		PA		16-1	29-11-11	D00576		24				D40806J		4				YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0510	24		PK		12-1	32-42-11	D40806J		1				D11130		3				YC051-YC055
0510	24		PK		12-2	32-42-11	D40806J		1				D11130		3				YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0511	24		PK		2-8	32-42-11	SP01502			S			D11130		2				YC051-YC055
0511	24		PK		2-9	32-42-11	SP01502			S			D11130		2				YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0512	24		PK		12-1	32-42-11	D40806J		2				D11130		6				YC051-YC055
0512	24		PK		12-2	32-42-11	D40806J		2				D11130		6				YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0513	24		PK		2-8	32-42-11	SP01504			S			D11130		5				YC051-YC055
0513	24		PK		2-9	32-42-11	SP01504			S			D11130		5				YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0515	24		PK		11-5	29-33-11	D00576		19				D48120P		A06				YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0516	24		PK		16-1	29-33-11	D00576		20				D40806J		7				YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0520	24		PK		1-9	24-34-11	C01341		5A	1A			GD00270		ST..	E			YC051-YD158

WIRE LIST

D280A108

91-21-11

Section W5500

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type
W5506	286A5506			P8 TO E/E BAY (continued)										
0520	24		PK		1-10	24-34-11	C01341	5A	1A		GD00270	ST..	E	YL951-YL968, YN231-YN236, YN501-YR328
0521	24		PK		26-3	24-34-11	C01341	3	1A		D40800P	26		YC051-YC052
0521	24		PK		25-9	24-34-11	C01341	3	1A		D40800P	26		YC053-YC055
0521	24		PK		26-4	24-34-11	C01341	3	1A		D40800P	26		YC056-YD158
0521	24		PK		26-2	24-34-11	C01341	3	1A		D40800P	26		YL951-YL968, YN231-YN236, YN501-YR328
0522	22		CQ		8-6	29-23-11	D40800P	27			D46128P	A03		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
0523	20		PA		7-2	32-35-11	D40800P	18			S01060	C	C	YC051-YC055
0523	20		PA		7-3	32-35-11	D40800P	18			S01060	C	C	YC056-YD158, YL951-YL968, YN231-YN236, YN501
0523	20		PA		7-5	32-35-11	D40800P	18			D15510	A		YR301-YR328
0524	20		PA		21-4	32-35-11	D40430P	4			S01060	NC	C	YC051-YC055
0524	20		PA		21-5	32-35-11	D40430P	4			S01060	NC	C	YC056-YD158, YL951-YL968, YN231-YN236, YN501
0524	20		PA		21-7	32-35-11	D40430P	4			D15510	B		YR301-YR328
0601	20		PA		18-1	47-30-11	D40674P	8			D40806J	30		YL951-YL968, YN231-YN236, YN501-YR328
0602	20		PA		18-1	47-30-11	D40674P	11			D40806J	33		YL951-YL968, YN231-YN236, YN501-YR328
1303	20		X1	EQ	25-6	74-11-11	D11288	12			D40430P	3		YC051-YC055
1303	20		X1	EQ	25-7	74-11-11	D11288	12			D40430P	3		YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1303Z				EQ	0-0	74-11-11	D11288	S/R			D40430P			AC YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1311	20		X1	EY	18-9	73-22-11	D40674P	13			D40430P	2		YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5500

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5506	286A5506				P8 TO E/E BAY (continued)										
1311	20	X1	EY		18-11	73-22-11	D40674P	13			D40430P	2			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
1311Z			EY		0-0	73-22-11	D40674P			EY	D40430P			AB	YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
2201B	22	X2	KA		4-4	24-22-11	D00576	16			TB0801X	B001	1A		YC051-YC055
2201B	22	X2	KA		4-6	24-22-11	D00576	16			TB0801X	B001	1A		YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
2201R	22	X2	KA		0-0	24-22-11	D00576	17			TB0801X	A001	1A		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
2201Z			KA		0-0	24-22-11	D00576	DED			GB00801	ST..	1A		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
2611B	24	Y2	SK		14-8	73-21-11	D40686P	6			D40430P	7			YC051-YD158
2611B	24	Y2	SK		14-10	73-21-11	D40686P	6			D40430P	7			YL951-YL968, YN231-YN236, YN501-YR328
2611R	24	Y2	SK		0-0	73-21-11	D40686P	7			D40430P	8			YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
2611Z			SK		0-0	73-21-11	D40686P			SK	D40430P			AA	YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
5501	24	B6			11-11	36-11-11	D40800P	5			D00576	10			YC051-YC055
5501	24	B6			12-0	36-11-11	D40800P	5			D00576	10			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328

WIRE LIST
D280A108

91-21-11
Section W5500
Page 11
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5506	286A5506			P8 TO E/E BAY (continued)											
5502	24		B6		10-5	36-11-11	D46128P	A09			D00576	11			YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
5503	24		B6		10-5	36-11-11	D46128P	A10			D00576	9			YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
5504	20		CQ		4-4	33-11-33	D01078	2			TB0801W	A005	1		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
5505	20		CQ		4-3	33-11-33	D01078	1			GD00805	AC..	1A		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
5506	20		PA		11-5	33-18-61	D40800P	6			TB0804Z	A021	1A		YC051-YD154
5506	20		PA		11-5	33-18-63	D40800P	6			TB0804Z	A021	1A		YD155-YD158, YL951-YL968, YN231-YN236, YN501-YR328
5507	20		PA		11-11	33-18-63	D40800P	7			D01078	6			YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
5508	20		PA		11-8	33-18-63	TB1806Y	B003	1A		D01078	17			YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
5509	20		PA		5-0	33-18-63	TB0804Z	A021	1A		D00576	2			YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
5510	20		PA		10-5	31-52-45	D01078	12			D46128P	A04			YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
5511	24		PK		8-3	21-42-11	D40802P	3			D48120P	A03			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5500

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5506	286A5506				P8 TO E/E BAY (continued)										
5511	24		PK		8-4	21-42-11	D40802P		3		D48120P	A03			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
5512	24		PK		8-4	21-43-21	D40800P		24		D46128P	A02			YC051-YC055
5512	24		PK		8-5	21-43-21	D40800P		24		D46128P	A02			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
5514	22		PA		8-3	21-27-31	D40802P		10		D48120P	A02			YC051-YC055
5514	22		PA		8-4	21-27-31	D40802P		10		D48120P	A02			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
5515	22		PA		8-4	21-25-11	D40800P		16		D46128P	A01			YC051-YC055
5515	22		PA		8-5	21-25-11	D40800P		16		D46128P	A01			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
5516	24		PK		25-1	36-21-11	D40430P		9		D40800P	4			YC051-YC055
5516	24		PK		25-3	36-21-11	D40430P		9		D40800P	4			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
5517	20		PA		17-11	30-71-11	D40802P		11		D40430P	28			YC051-YC055
5517	20		PA		18-1	30-71-11	D40802P		11		D40430P	28			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
5518	20		PA		17-11	30-71-11	D40802P		12		D40430P	29			YC051-YC055
5518	20		PA		18-1	30-71-11	D40802P		12		D40430P	29			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
5519	20		PA		17-11	30-71-11	D40802P		13		D40430P	30			YC051-YC055
5519	20		PA		18-1	30-71-11	D40802P		13		D40430P	30			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W5500

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W5506	286A5506				P8 TO E/E BAY (continued)												
5520	24		PK		12-5	21-27-31	D40800P		22			D48120P	A01			YC051-YC055	
5520	24		PK		12-6	21-27-31	D40800P		22			D48120P	A01			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
5523	24		PK		11-0	21-43-21	D46128P		B04			D48120P	B03			YL951-YL968, YN231-YN236, YN501-YR328	
6001	20		PA		13-11	34-41-11	D40800P		37			D40674P	9			YC053-YD157	
6001	20		CQ		13-11	34-41-11	D40800P		37			D40674P	9			YD158, YL951-YL968, YN231-YN236, YN501-YR328	
6001R	22		PH		24-1	26-11-31	D01078		15			D40430P	23			YC051-YC055	
6001R	22		PH		24-2	26-11-31	D01078		15			D40430P	23			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
6002R	20		PH		24-1	26-11-31	D01078		28			D40430P	24			YC051-YC055	
6002R	20		PH		24-2	26-11-31	D01078		28			D40430P	24			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
6003R	20		PH		24-1	26-11-31	D01078		7			D40430P	25			YC051-YC055	
6003R	20		PH		24-2	26-11-31	D01078		7			D40430P	25			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
6004R	20		PH		4-7	26-11-31	D01078		27			TB0804X	B001	1A		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
6005R	20		PH		4-7	26-11-31	D01078		14			TB0804X	A001	1A		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
6006	20		CQ		11-11	76-21-11	D40800P		8			D00576	30			YC051-YC055	

WIRE LIST

D280A108

91-21-11

Section W5500

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5506	286A5506				P8 TO E/E BAY (continued)										
6006	20		CQ		12-0	76-21-11	D40800P	8			D00576	30			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6009	24		B6		27-6	76-21-11	D11288	5			D40686P	8			YC051-YC055
6009	24		B6		27-7	76-21-11	D11288	5			D40686P	8			YC056-YD158
6009	24		B6		27-9	76-21-11	D11288	5			D40686P	8			YL951-YL968, YN231-YN236, YN501-YR328
6010	24		B6		27-6	76-21-11	D11288	4			D40686P	9			YC051-YC055
6010	24		B6		27-7	76-21-11	D11288	4			D40686P	9			YC056-YD158
6010	24		B6		27-9	76-21-11	D11288	4			D40686P	9			YL951-YL968, YN231-YN236, YN501-YR328
6011	20		PA		2-6	76-21-11	D11288	15			GD00800	DC..	1A		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6012	20		CQ		11-5	76-21-11	D00576	29			D48120P	A07			YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6013R	20		9P		4-10	76-21-11	D00576	31			TB0804X	A015	1A		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6014R	22		PH		16-0	26-12-11	D01078	20			D40806J	12			YC051-YC055
6014R	22		PH		16-1	26-12-11	D01078	20			D40806J	12			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6015R	22		PH		7-10	26-11-11	D40800P	9			SM00010		S		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6016R	22		PH		18-4	26-11-11	D40430P	16			SM00010		S		YC051-YC055

WIRE LIST
D280A108

91-21-11
Section W5500
Page 15
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5506	286A5506				P8 TO E/E BAY (continued)										
6016R	22		PH		18-5	26-11-11	D40430P	16			SM00010		S		YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6017R	22		PH		6-10	26-11-11	D01078	31			SM00010		S		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6018R	22		PH		24-1	26-11-11	D01078	13			D40430P	10			YC051-YC055
6018R	22		PH		24-2	26-11-11	D01078	13			D40430P	10			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6019R	22		PH		24-1	26-11-11	D01078	19			D40430P	11			YC051-YC055
6019R	22		PH		24-2	26-11-11	D01078	19			D40430P	11			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6020R	22		PH		24-1	26-11-11	D01078	16			D40430P	12			YC051-YC055
6020R	22		PH		24-2	26-11-11	D01078	16			D40430P	12			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6021R	22		PH		24-1	26-11-11	D01078	8			D40430P	13			YC051-YC055
6021R	22		PH		24-2	26-11-11	D01078	8			D40430P	13			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6022R	22		PH		24-1	26-11-11	D01078	25			D40430P	14			YC051-YC055
6022R	22		PH		24-2	26-11-11	D01078	25			D40430P	14			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6023R	22		PH		24-1	26-11-11	D01078	24			D40430P	15			YC051-YC055
6023R	22		PH		24-2	26-11-11	D01078	24			D40430P	15			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W5500

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Description Fam	FT-IN	Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W5506	286A5506			P8 TO E/E BAY (continued)											
6024R	22		PH		1-5	26-11-11	D01078	10			D00576	27			YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6025R	22		PH		1-5	26-11-11	D01078	11			D00576	1			YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6026R	22		PH		3-11	26-11-11	D00576	28			GD00809	DC..	1A		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6027	20		CQ		11-11	28-21-11	D00576	22			D40800P	14			YC051-YC055
6027	20		CQ		12-0	28-21-11	D00576	22			D40800P	14			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6028	20		PA		8-10	28-21-11	D00576	23			D11288	9			YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6029	20		CQ		5-3	28-21-11	D00576	21			SP00656		S		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6030	20		PA		7-1	28-21-11	D11288	7			SP00656		S		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6031	20		PA		12-10	28-21-11	D11288	8			D48120P	A04			YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6033	20		PA		13-10	78-34-11	D00576	5			D40802P	4			YC051-YC055
6033	20		PA		13-11	78-34-11	D00576	5			D40802P	4			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328

WIRE LIST
D280A108

91-21-11
Section W5500
Page 17
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5506	286A5506				P8 TO E/E BAY (continued)										
6034	20		PA		7-11	78-34-11	D00576	6			SM00018		S		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6035	20		PA		22-2	78-34-11	D11130	15			D40950P	A01			YC051-YC055
6035	20		PA		22-9	78-34-11	D11130	15			D40950P	A01			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6036	20		PA		3-6	78-34-11	D11130	14			SM00018		S		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6037	20		PA		24-2	78-34-11	D40950P	A04			SM00018		S		YC051-YC055
6037	20		PA		24-9	78-34-11	D40950P	A04			SM00018		S		YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6038	20		PA		22-2	78-34-11	D11130	9			D40950P	A05			YC051-YC055
6038	20		PA		22-9	78-34-11	D11130	9			D40950P	A05			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6039	20		PA		22-2	78-34-11	D11130	8			D40950P	A03			YC051-YC055
6039	20		PA		22-9	78-34-11	D11130	8			D40950P	A03			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6040	20		PA		7-11	78-34-11	D11130	7			D40674P		4		YC051-YC055
6040	20		PA		8-0	78-34-11	D11130	7			D40674P		4		YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6041	20		PA		28-8	78-34-11	D10171	5			D40950P	A02			YC051-YC055
6041	20		PA		29-2	78-34-11	D10171	5			D40950P	A02			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W5500

Page 18

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W5506	286A5506				P8 TO E/E BAY (continued)											
6042	20		PA		9-5	78-34-11	D10171		4		SM00018		S		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
6043	18		PA		8-6	78-32-51	D40802P		5	18	TB1806V	B015	1		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
6045	20		PA		15-3	74-11-11	D11288		11		D40802P		6		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
6046	20		PA		21-9	78-34-11	D40950P		A06		D40674P		3		YC051-YC055	
6046	20		PA		22-4	78-34-11	D40950P		A06		D40674P		3		YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
6047	24		B6		19-11	76-21-11	D40802P		7		D40686P		10		YC051-YC055	
6047	24		B6		20-1	76-21-11	D40802P		7		D40686P		10		YC056-YD158	
6047	24		B6		20-3	76-21-11	D40802P		7		D40686P		10		YL951-YL968, YN231-YN236, YN501-YR328	
6048R	22		PH		5-5	26-11-21	D40800P		10		SM00028		S		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
6049R	22		PH		9-2	26-11-21	D40806J		28		SM00028		S		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
6050R	22		PH		7-11	26-11-21	D01078		5		SM00028		S		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
6051R	22		PH		17-10	26-11-21	D01078		21		D40804P		2		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328	
6052R	22		PH		16-0	26-11-21	D01078		29		D40806J		32		YC051-YC055	

WIRE LIST
D280A108

91-21-11
Section W5500
Page 19
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W5506	286A5506			P8 TO E/E BAY (continued)											
6052R	22		PH		16-1	26-11-21	D01078		29			D40806J	32		YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6053R	22		PH		24-1	26-11-21	D01078		18			D40430P	26		YC051-YC055
6053R	22		PH		24-2	26-11-21	D01078		18			D40430P	26		YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6054R	22		PH		12-4	26-21-11	D40800P		11			D48118P	B02		YC051-YC055
6054R	22		PH		12-5	26-21-11	D40800P		11			D48118P	B02		YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6055R	22		PH		12-4	26-21-11	D40800P		12			D48118P	B03		YC051-YC055
6055R	22		PH		12-5	26-21-11	D40800P		12			D48118P	B03		YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6056R	22		PH		11-5	26-21-11	D00576		12			D48118P	A07		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6057R	22		PH		11-5	26-21-11	D00576		14			D48118P	B04		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6058R	22		PH		11-5	26-21-11	D00576		4			D48118P	B05		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6059R	22		PH		11-5	26-21-11	D00576		8			D48118P	B06		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6060R	22		PH		11-4	26-21-11	D01078		3			D48118P	B08		YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5500

Page 20

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY	Description Fam FT-IN Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W5506	286A5506	P8 TO E/E BAY (continued)									
6060R	22 PH	11-5 26-21-11	D01078	3			D48118P	B08			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6061R	22 PH	12-4 26-21-11	D40800P	13			D48118P	B07			YC051-YC055
6061R	22 PH	12-5 26-21-11	D40800P	13			D48118P	B07			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6062R	22 PH	4-1 26-21-11	D00576	7			SM00002		S		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6063R	22 PH	4-1 26-21-11	D00576	3			SM00004		S		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6064R	22 PH	11-5 26-21-11	D00576	18			D48118P	B09			YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6065R	22 PH	11-5 26-21-11	D00576	13			D48118P	B10			YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6066R	22 PH	20-7 26-21-11	D40430P	21			SM00002		S		YC051-YC055
6066R	22 PH	20-8 26-21-11	D40430P	21			SM00002		S		YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6067R	22 PH	20-7 26-21-11	D40430P	22			SM00004		S		YC051-YC055
6067R	22 PH	20-8 26-21-11	D40430P	22			SM00004		S		YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6070R	22 PH	4-1 26-21-11	D01078	22			SM00004		S		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328

WIRE LIST
D280A108

91-21-11
Section W5500
Page 21
Nov 12/2012

Bundle No.	Part Number			Description	Diagram	From				To				Effectivity	
Wire No.	GA	CO	TY			Fam	FT-IN	Equip	Term	Type	Splice	Equip	Term		Type
W5506	286A5506			P8 TO E/E BAY (continued)											
6071R	22		PH		4-1	26-21-11	D01078		4		SM00002		S		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6072R	22		PH		11-4	26-21-11	D01078		30		D48118P		A03		YC051-YC055
6072R	22		PH		11-5	26-21-11	D01078		30		D48118P		A03		YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6073R	22		PH		11-4	26-21-11	D01078		23		D48118P		A02		YC051-YC055
6073R	22		PH		11-5	26-21-11	D01078		23		D48118P		A02		YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6074R	22		PH		11-4	26-21-11	D01078		26		D48118P		A01		YC051-YC055
6074R	22		PH		11-5	26-21-11	D01078		26		D48118P		A01		YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6075R	22		PH		24-1	26-21-11	D01078		9		D40430P		17		YC051-YC055
6075R	22		PH		24-2	26-21-11	D01078		9		D40430P		17		YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6076R	22		PH		18-5	26-21-11	D40430P		18		D48118P		A04		YC051-YC055
6076R	22		PH		18-7	26-21-11	D40430P		18		D48118P		A04		YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6077R	22		PH		18-5	26-21-11	D40430P		19		D48118P		A05		YC051-YC055
6077R	22		PH		18-7	26-21-11	D40430P		19		D48118P		A05		YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6078R	22		PH		18-5	26-21-11	D40430P		20		D48118P		A06		YC051-YC055
6078R	22		PH		18-7	26-21-11	D40430P		20		D48118P		A06		YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W5500

Page 22

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5506	286A5506				P8 TO E/E BAY (continued)										
6079R	22		PH		11-10	26-11-21	SM00028		S		D40804P	3			YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328 YD158
6080	22		CQ		11-11	26-23-11	TB0801X	A002	1A		D40674P	10			YR315-YR316, YR319
6080	22		CQ		11-11	26-23-11	D40674P	10			TB0801X	A002	1A		YR317
6080	22		CQ		11-11	SPARE	D40674P	CAP	Y		TB0801X	A002	1A		YC051-YC055
6081	20		CQ		8-6	73-22-11	D40674P	12			D40802P	14			YC056-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6081	20		CQ		8-7	73-22-11	D40674P	12			D40802P	14			YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6082	20		PA		9-9	28-21-11	D48120P	A05			SP00656		S		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6083	20		PA		9-4	78-35-11	D40802P	9			D10167	2			YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6084	20		PA		6-11	78-35-11	D10167	3			D48120P	B01			YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6085	20		PA		4-10	78-35-11	D10167	1			GD00815	ST..	1A		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6088	22		PA		12-8	28-41-11	D40800P	15			TB1806X	B005	1A		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6089	20		PA		16-7	76-21-11	D40806J	40			D48120P	A08			YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6091	18		PA		12-8	23-32-12	D40800P	38	18		TB1806V	A013	1		YC051-YD157
6092	20		PA		12-8	23-32-12	D40800P	39			TB1806X	B006	1A		YC051-YD157
6501	22		PA		20-9	23-31-06	D40686P	3			TB1806Y	B001	1A		YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5500

Page 23

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5506		286A5506			P8 TO E/E BAY (continued)											
6501		22		PA		20-10	23-31-06	D40686P		3		TB1806Y	B001	1A		YC056-YD158
6501		22		PA		21-0	23-31-06	D40686P		3		TB1806Y	B001	1A		YL951-YL968, YN231-YN236
6501		22		PA		21-0	44-21-22	D40686P		3		TB1806Z	A009	1A		YN501-YR314, YR317-YR318, YR320-YR328
6501		22		PA		21-0	23-31-06	D40686P		3		TB1806Z	A009	1A		YR315-YR316, YR319
6504		24		PK		18-1	34-61-26	D40674P		5		D40806J	13			YC059-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6505		24		PK		18-1	34-61-26	D40674P		6		D40806J	14			YC059-YD158, YL951-YL968, YN231-YN236, YN501-YR328
6506		20		PA		8-5	23-34-01	D40800P		31		D46128P	B10			YC060-YD158
6506		20		CQ		8-5	23-34-01	D40800P		31		D46128P	B10			YL951-YL968, YN231-YN236
6506		20		PA		8-5	SPARE	D40800P		31		D46128P	B10			YN501-YR328
FRA1						0-0	73-21-11	D40430P		S/R		D40430P			AA	YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
FRA2						0-0	73-21-11	D40430P		31		D40430P			AA	YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
FRA3						0-0	73-22-11	D40430P		S/R		D40430P			AB	YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
FRA4						0-0	73-22-11	D40430P		6		D40430P			AB	YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
FRA5						0-0	74-11-11	D40430P		S/R		D40430P			AC	YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W5500

Page 24

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5506	286A5506				P8 TO E/E BAY (continued)											
FRA6					0-0	74-11-11		D40430P		5		D40430P		AC		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
FRE1					0-0	73-22-11		D40674P		14		D40674P		EY		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
FRE2					0-0	73-22-11		D40674P		S/R		D40674P		EY		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
FRS5					0-0	73-21-11		D40686P		5		D40686P		SK		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328
FRS6					0-0	73-21-11		D40686P		S/R		D40686P		SK		YC051-YD158, YL951-YL968, YN231-YN236, YN501-YR328

WIRE LIST
D280A108

91-21-11
Section W5500
Page 25 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5510		286A5510					P8 TO E/E BAY AND J BOX.									
0001		22		PA		31-9	35-21-11	D40496J			1	D40688P			1	ALL
0002		16		PA		31-9	35-21-11	D40496J			2	D40688P			2	ALL
0003		16		PA		31-9	35-21-11	D40496J			3	D40688P			3	ALL
0004		16		PA		31-9	35-21-11	D40496J			4	D40688P			4	ALL
0005		16		PA		31-9	35-21-11	D40496J			5	D40688P			5	ALL
0006		22		PA		31-9	35-21-11	D40496J			12	D40688P			6	ALL
0010		20		PA		17-5	23-71-01	D40496J			19	D40672P			23	YC051-YC055
0010		20		PA		17-7	23-71-01	D40496J			19	D40672P			23	YC056-YR328
0011		24		PK		16-4	23-71-01	D40428P		A04		D40672P			9	YC051-YC055
0011		24		PK		16-3	23-71-01	D40428P		A04		D40672P			9	YC056-YR328
0012		24		PK		16-4	23-71-01	D40428P		A08		D40672P			12	YC051-YC055
0012		24		PK		16-3	23-71-01	D40428P		A08		D40672P			12	YC056-YR328
0018		20		PA		21-7	28-23-11	D40428P		B05		D46130P		B01		YD158-YR328
0019		20		PA		21-7	28-23-11	D40428P		A07		D46130P		B02		YD158-YR328
0020		20		PA		21-7	28-23-11	D40428P		A03		D46130P		B03		YD158-YR328
0023		24		PK		16-0	21-43-21	D40672P		15		D40698P			35	YC060-YC064
0024		24		PK		16-0	21-43-21	D40672P		11		D40698P			34	YC060-YC064
0042		20		PA		27-5	28-23-11	D40428P		G		D40496J			6	YD160-YR328
0043		20		PA		27-5	28-23-11	D40428P		H		D40496J			7	YD160-YR328
0044		20		PA		21-7	28-23-11	D40428P		K		D46130P		B05		YD160-YR328
0500		22		PA		7-9	34-41-11	D11128		18		D40672P			17	YC053-YC055
0500		22		PA		8-1	34-41-11	D11128		18		D40672P			17	YC056-YC059, YC065-YR328 YC060-YC064
0500		22		PA		8-0	34-41-11	D11128		18		D40672P			17	YC060-YC064
0501		18		PA		31-9	24-11-11	D40496J		11		D40688P			7	ALL
0502		22		PA		5-3	27-62-11	D11128		1		D46130P		A03		YC051-YC055
0502		22		PA		5-5	27-62-11	D11128		1		D46130P		A03		YC056-YC059, YC065-YR328 YC060-YC064
0502		22		PA		5-4	27-62-11	D11128		1		D46130P		A03		YC051-YC055
0526		22		PA		5-3	31-53-11	D11128		16		D46130P		A02		YC056-YC059, YC065-YR328 YC060-YC064
0526		22		PA		5-5	31-53-11	D11128		16		D46130P		A02		YC051-YC055
0526		22		PA		5-4	31-53-11	D11128		16		D46130P		A02		YC056-YC059, YC065-YR328 YC060-YC064
0540		22		PA		4-8	31-53-11	D11128		17		GD00813		DC.. 1A		YC051-YC055, YC060-YC064
0540		22		PA		4-9	31-53-11	D11128		17		GD00813		DC.. 1A		YC056-YC059, YC065-YR328 YC051-YC055
0570		22		PA		6-4	32-64-21	D11128		3		D48122P		A09		YC060-YC064

WIRE LIST

D280A108

91-21-11

Section W5510

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W5510	286A5510				P8 TO E/E BAY AND J BOX. (continued)										
0570	22		PA		6-5	32-64-21	D11128		3		D48122P	A09			YC056-YC059, YC065-YR328
0571	22		PA		4-8	32-64-21	D11128		2		GD00813	DC..	1A		YC051-YC055, YC060-YC064
0571	22		PA		4-9	32-64-21	D11128		2		GD00813	DC..	1A		YC056-YC059, YC065-YR328
0572	22		PA		6-4	32-64-21	D11128		24		D48122P	A10			YC051-YC055, YC060-YC064
0572	22		PA		6-5	32-64-21	D11128		24		D48122P	A10			YC056-YC059, YC065-YR328
0573	22		PA		4-8	32-64-21	D11128		23		GD00813	DC..	1A		YC051-YC055, YC060-YC064
0573	22		PA		4-9	32-64-21	D11128		23		GD00813	DC..	1A		YC056-YC059, YC065-YR328
0574	18		CQ		13-5	24-11-11	D40688P		8		D40428P	F			YC051-YD158
0574	18		CQ		13-10	24-11-11	D40688P		8		D40428P	F			YD160-YR328
0575	22		CQ		17-5	27-62-11	D40496J		17		D40672P	14			YC051-YC055
0575	22		CQ		17-7	27-62-11	D40496J		17		D40672P	14			YC056-YR328
0576	22		CQ		17-5	27-62-11	D40496J		18		D40672P	13			YC051-YC055
0576	22		CQ		17-7	27-62-11	D40496J		18		D40672P	13			YC056-YR328
1301	20		X1	EN	11-11	74-11-11	D11286		12		D48122P	B01			YC051-YC055
1301	20		X1	EN	12-0	74-11-11	D11286		12		D48122P	B01			YC056-YR328
1301Z				EN	0-0	74-11-11	D11286		S/R		D48122P	PERG	1F		ALL
2201B	22		X2	KA	21-0	24-22-11	D40428P		B06		TB0801X	B001	1A		YC051-YC055
2201B	22		X2	KA	21-2	24-22-11	D40428P		B06		TB0801X	B001	1A		YC056-YR328
2201R	22		X2	KA	0-0	24-22-11	D40428P		A06		TB0801X	A001	1A		ALL
2201Z				KA	0-0	24-22-11	D40428P		PERG	1F	GB00801	ST..	1A		ALL
2202B	22		X2	KB	16-2	24-22-31	D40428P		A10		D48122P	A05			ALL
2202R	22		X2	KB	0-0	24-22-31	D40428P		B10		D48122P	A04			ALL
2202Z				KB	0-0	24-22-31	D40428P		DED		D48122P	DED			ALL
2203B	24		PL	KC	27-5	24-33-11	D40428P		A02		D40496J	13			ALL
2203R	24		PL	KC	0-0	24-33-11	D40428P		B02		D40496J	14			ALL
2601B	18		X2	SA	6-11	78-32-51	D40672P		18	18	TB1808V	B005	1		YC051-YC055
2601B	18		X2	SA	7-1	78-32-51	D40672P		18	18	TB1808V	B005	1		YC056-YR328
2601R	18		X2	SA	0-0	78-32-51	D40672P		30	18	TB1808V	A005	1		ALL
2601Z				SA	0-0	78-32-51	D40672P		S/R		GB01808	ST..	1A		ALL
2602B	18		X2	SB	6-11	78-32-51	D40672P		20	18	TB1808V	B007	1		YC051-YC055
2602B	18		X2	SB	7-1	78-32-51	D40672P		20	18	TB1808V	B007	1		YC056-YR328
2602R	18		X2	SB	0-0	78-32-51	D40672P		19	18	TB1808V	A007	1		ALL

WIRE LIST

D280A108

91-21-11

Section W5510

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5510		286A5510			P8 TO E/E BAY AND J BOX. (continued)											
2602Z					SB	0-0	78-32-51	D40672P	S/R			GB01808	ST..	1A		ALL
5501		22		PA		21-7	21-27-31	D40428P	B01			D46130P	A01			ALL
5502		24		PK		6-2	21-43-21	D40672P	10			D48122P	A02			YC051-YC055
5502		24		PK		6-5	21-43-21	D40672P	10			D48122P	A02			YC056-YR328
5503		24		PK		6-2	21-43-21	D40672P	11			D48122P	A03			YC051-YC055
5503		24		PK		6-5	21-43-21	D40672P	11			D48122P	A03			YC056-YC059, YC065-YD158
5503		24		PK		6-5	SPARE	D40672P	11			D48122P	A03			YD160-YR328
5510		24		PK		6-2	21-43-21	D40672P	15			D48122P	B09			YC051-YC055
5510		24		PK		6-5	21-43-21	D40672P	15			D48122P	B09			YC056-YC059, YC065-YD158
5510		24		PK		6-5	SPARE	D40672P	15			D48122P	B09			YD160-YR328
5511		24		PK		6-2	21-43-21	D40672P	16			D48122P	B08			YC051-YC055
5511		24		PK		6-5	21-43-21	D40672P	16			D48122P	B08			YC056-YR328
6001		20		CQ		2-6	76-21-11	D11286	15			GD00800	DC..	1A		YC051-YC055
6001		20		CQ		2-7	76-21-11	D11286	15			GD00800	DC..	1A		YC056-YR328
6002		24		B6		11-11	76-21-11	D11286	5			D48122P	B03			YC051-YC055
6002		24		B6		12-0	76-21-11	D11286	5			D48122P	B03			YC056-YR328
6003		24		B6		11-11	76-21-11	D11286	4			D48122P	B04			YC051-YC055
6003		24		B6		12-0	76-21-11	D11286	4			D48122P	B04			YC056-YR328
6004		20		CQ		11-11	74-11-11	D11286	11			D48122P	B02			YC051-YC055
6004		20		CQ		12-0	74-11-11	D11286	11			D48122P	B02			YC056-YR328
6005		24		PK		11-11	76-21-11	D11286	8			D48122P	B06			YC051-YC055
6005		24		PK		12-0	76-21-11	D11286	8			D48122P	B06			YC056-YR328
6006		20		PA		11-11	76-21-11	D11286	7			D48122P	B07			YC051-YC055
6006		20		PA		12-0	76-21-11	D11286	7			D48122P	B07			YC056-YR328
6007		22		PA		15-11	30-11-11	D48122P	A07			D40496J	10			ALL
6008		18		PA		6-11	78-32-51	D40672P	1	18		TB1806V	B015	1		YC051-YC055
6008		18		PA		7-2	78-32-51	D40672P	1	18		TB1806V	B015	1		YC056-YR328
6009		22		PA		7-1	78-32-51	D11128	7			TB1806V	B015	1		YC051-YC055, YC060-YC064
6009		22		PA		7-2	78-32-51	D11128	7			TB1806V	B015	1		YC056-YC059, YC065-YR328
6011R		20		9P		7-11	76-21-11	TB0804X	A015	1A		D11286	9			ALL
6013		20		PA		16-2	28-21-11	D40428P	A01			D48122P	A06			ALL
6015		22		PA		17-5	23-15-15	D40672P	21			D40496J	15			YC051-YC055
6015		22		PA		17-7	23-15-15	D40672P	21			D40496J	15			YC056-YD157
6016		22		PA		17-5	23-15-15	D40672P	22			D40496J	16			YC051-YC055
6016		22		PA		17-7	23-15-15	D40672P	22			D40496J	16			YC056-YD157

WIRE LIST

D280A108

91-21-11

Section W5510

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W5510	286A5510				P8 TO E/E BAY AND J BOX. (continued)											
6018	22		CQ		21-7	21-27-21		D46130P	A10			D40428P	A05			YD160-YR328
6019	22		CQ		21-7	21-27-21		D46130P	B10			D40428P	B03			YD160-YR328
6086	22		PA		6-4	30-11-11		D11128	10			D48122P	A08			YC051-YC055, YC060-YC064
6086	22		PA		6-5	30-11-11		D11128	10			D48122P	A08			YC056-YC059, YC065-YR328
6087	22		PA		4-8	30-11-11		D11128	11			GD00813	DC..	1A		YC051-YC055, YC060-YC064
6087	22		PA		4-9	30-11-11		D11128	11			GD00813	DC..	1A		YC056-YC059, YC065-YR328
6088	22		PA		7-9	78-32-51		D11128	14			D40672P	7			YC051-YC055
6088	22		PA		8-1	78-32-51		D11128	14			D40672P	7			YC056-YC059, YC065-YR328
6088	22		PA		8-0	78-32-51		D11128	14			D40672P	7			YC060-YC064
6089	22		PA		7-9	78-32-51		D11128	8			D40672P	2			YC051-YC055
6089	22		PA		8-1	78-32-51		D11128	8			D40672P	2			YC056-YC059, YC065-YR328
6089	22		PA		8-0	78-32-51		D11128	8			D40672P	2			YC060-YC064
6090	22		PA		17-5	78-32-51		D40672P	6			D40496J	8			YC051-YC055
6090	22		PA		17-7	78-32-51		D40672P	6			D40496J	8			YC056-YR328
6091	22		PA		17-5	78-32-51		D40672P	8			D40496J	9			YC051-YC055
6091	22		PA		17-7	78-32-51		D40672P	8			D40496J	9			YC056-YR328
W5514	286A5514				FLIGHT DECK PANEL LIGHTING (SA2)											
0001	22		PA		25-10	35-21-11		D40830P	6			D40826J	14			YC051-YD158, YL951-YR328
0002	16		PA		25-10	35-21-11		D40830P	7			D40826J	15			YC051-YD158, YL951-YR328
0003	16		PA		25-10	35-21-11		D40830P	8			D40826J	19			YC051-YD158, YL951-YR328
0004	16		PA		25-10	35-21-11		D40830P	9			D40826J	23			YC051-YD158, YL951-YR328
0005	16		PA		25-10	35-21-11		D40830P	10			D40826J	27			YC051-YD158, YL951-YR328
0014	22		CQ		16-8	21-33-11		D46100P	34			D01172	5			YC060-YC064
0014	22		CQ		8-7	21-33-11		D01172	5			SP05006		9		YL952-YL999, YN232-YR328
0015	22		CQ		16-8	21-33-11		D46100P	35			D01172	3			YC060-YC064

WIRE LIST

D280A108

91-21-11

Section W5510

Page 4

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W5514	286A5514				FLIGHT DECK PANEL LIGHTING (SA2) (continued)											
0015	22		CQ		8-7	21-33-11	D01172		3		SP05008		9		YL952-YL999, YN232-YR328	
0028	20		CQ		10-6	44-21-10	D40822P		22		D46104P	35			YN501-YR328	
0029	20		PA		10-6	44-21-10	D40822P		21		D46104P	36			YN501-YR328	
0045	22		CQ		4-10	52-51-11	D01344		45		TB0803X	B001	1A		YC051-YD154	
0502	24		B6		18-6	SPARE	D40824P		28		D40826J	7			YC051-YD158, YL951-YR328	
0503	24		B6		18-6	SPARE	D40824P		29		D40826J	16			YC051-YD158, YL951-YR328	
0504	24		B6		18-6	SPARE	D40824P		30		D40826J	17			YC051-YD158, YL951-YR328	
0505	24		B6		18-6	SPARE	D40824P		31		D40826J	18			YC051-YD158, YL951-YR328	
0511	24		PK		20-3	32-44-11	D40826J		3		S00100	1NC	B		YC051-YD158, YL951-YR328	
0513	24		PK		20-2	32-44-11	D40826J		4		S00100	1NO	B	*	YC051-YD157	
0513	24		PK		20-2	32-44-11	D40826J		4		S00100	1NO	B		YD158, YL951-YR328	
0514	24		PK		12-7	32-44-11	D40826J		1		D46104P	29			YC051-YD158, YL951-YR328	
0516	24		PK		12-7	32-44-11	D40826J		2		D46104P	30			YC051-YD158, YL951-YR328	
0517	24		PK		12-7	32-44-11	D40826J		5		D46104P	31			YC051-YD158, YL951-YR328	
0520	20		PA		15-1	32-44-11	D40822P		13		S00100	1C	B		YC051-YD158, YL951-YR328	
0521	24		PK		9-0	32-44-11	D02866		26		D46104P	28			YC051-YD158, YL951-YR328	
0556	22		PA		15-5	32-64-21	D00940		2		D46104P	32			YC051-YD158, YL951-YR328	
1001	22		X1	AA	9-3	22-14-11	D00940		4		SP02135		S		YC051-YD158, YL951-YR328	
1001Z				AA	0-0	22-14-11	D00940		DED		SP02135	REF		AB	YC051-YD158, YL951-YR328	
1002	22		PA		15-4	23-42-11	D00940		9		TB0608X	B003	1A		YL951-YR328	
5501	20		PA		3-7	31-51-11	D00940		6		GD0911B	DC..	1A		YC051-YD158, YL951-YR328	
5502	22		PA		10-1	31-51-11	D00940		5		D40822P	3			YC051-YD158, YL951-YR328	

WIRE LIST

D280A108

91-21-11

Section W5510

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5514	286A5514				FLIGHT DECK PANEL LIGHTING (SA2) (continued)										
5503	20		CQ		13-1	33-18-21	D01344		8		D40824P		22		YC051-YD158, YL951-YR328
5504	20		CQ		13-2	33-18-21	D02866		46		D40824P		24		YC051-YD158, YL951-YR328
5505	20		PA		11-4	33-18-51	D40822P		1		TB1806Y	B003	1A		YC051-YD158, YL951-YR328
5506	20		PA		8-1	33-18-51	D01344		1		D40822P		2		YC051-YD158, YL951-YR328
5507	20		PA		13-1	33-18-51	D01344		4		D40824P		7		YC051-YD158, YL951-YR328
5508	20		PA		11-0	33-18-61	D40822P		8		TB0803Y	A013	1A		YC051-YD154
5509	20		CQ		11-0	33-18-61	D40822P		9		TB0803Z	A005	1A		YC051-YD158, YL951-YR328
5510	20		CQ		11-0	33-18-61	D40822P		10		TB0803Z	B005	1A		YC051-YD158, YL951-YR328
5511	20		CQ		11-0	33-18-61	D40822P		11		TB0803Y	B015	1A		YC051-YD158, YL951-YR328
5512	20		CQ		4-10	33-18-61	D02866		42		TB0803Z	B005	1A		YC051-YD158, YL951-YR328
5513	20		PA		6-7	33-18-61	D01346		42		TB1806Y	B003	1A		YC051-YD154
5514	20		PA		4-10	33-18-61	D01344		46		TB0803X	A001	1A		YC051-YD154
5515	20		CQ		4-10	33-18-61	D02866		9		TB0803X	A002	1A		YC051-YD158, YL951-YR328
5516	20		CQ		8-1	31-52-11	D01344		2		D40822P		7		YC051-YD158, YL951-YR328
5517	20		CQ		13-1	31-52-11	D01344		10		D40824P		14		YC051-YD158, YL951-YR328
5518	20		CQ		4-5	31-52-11	D01346		2		SM00008		S		YC051-YD158, YL951-YR328
5519	20		CQ		4-5	31-52-11	D01346		1		SM00008		S		YC051-YD158, YL951-YR328
5520	20		CQ		4-5	31-52-11	D01346		3		SM00006		S		YC051-YD158, YL951-YR328
5521	20		CQ		10-4	31-52-11	D40826J		28		SM00006		S		YC051-YD158, YL951-YR328
5522	20		CQ		9-3	31-52-11	D40824P		12		SM00008		S		YC051-YD158, YL951-YR328
5523	20		CQ		9-3	31-52-11	D40824P		11		SM00006		S		YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5510

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5514	286A5514				FLIGHT DECK PANEL LIGHTING (SA2) (continued)										
5524	20		CQ		15-6	31-52-11	D40824P	13			D46104P	5			YC051-YD158, YL951-YR328
5525	20		CQ		9-0	31-52-21	D01346	9			D46104P	6			YC051-YD158, YL951-YR328
5526	20		CQ		15-6	31-52-21	D40824P	2			D46104P	7			YC051-YD158, YL951-YR328
5527	20		CQ		9-0	31-52-25	D01346	13			D46104P	8			YC051-YD158, YL951-YR328
5528	20		CQ		15-6	31-52-25	D40824P	1			D46104P	9			YC051-YD158, YL951-YR328
5529	20		CQ		9-0	31-52-31	D01346	4			D46104P	10			YC051-YD158, YL951-YR328
5530	20		CQ		15-6	31-52-31	D40824P	16			D46104P	11			YC051-YD158, YL951-YR328
5531	20		CQ		9-0	31-52-35	D01346	21			D46104P	12			YC051-YD158, YL951-YR328
5532	20		CQ		15-6	31-52-35	D40824P	17			D46104P	13			YC051-YD158, YL951-YR328
5533	20		CQ		9-0	31-52-41	D01346	11			D46104P	14			YC051-YD158, YL951-YR328
5534	20		CQ		15-6	31-52-41	D40824P	18			D46104P	15			YC051-YD158, YL951-YR328
5535	20		CQ		5-2	31-52-45	D01346	5			TB0804Y	A005	1A		YC051-YD158, YL951-YR328
5536	20		CQ		16-3	31-52-45	D40824P	6			TB0804Y	A005	1A		YC051-YD158, YL951-YR328
5537	20		CQ		9-0	31-52-51	D01346	15			D46104P	16			YC051-YD158, YL951-YR328
5538	20		CQ		15-6	31-52-51	D40824P	4			D46104P	17			YC051-YD158, YL951-YR328
5539	20		CQ		9-0	31-52-55	D01346	19			D46104P	18			YC051-YD158, YL951-YR328
5540	20		CQ		15-6	31-52-55	D40824P	3			D46104P	19			YC051-YD158, YL951-YR328
5541	20		CQ		9-0	31-52-61	D01346	24			D46104P	20			YC051-YD158, YL951-YR328
5542	20		CQ		15-6	31-52-61	D40824P	5			D46104P	21			YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5510

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5514	286A5514				FLIGHT DECK PANEL LIGHTING (SA2) (continued)										
5543	20		CQ		9-0	31-52-65	D01346		7		D46104P		22		YC051-YD158, YL951-YR328
5544	20		CQ		15-6	31-52-65	D40824P		8		D46104P		33		YC051-YD158, YL951-YR328
5545	20		CQ		4-5	31-52-71	D01346		25		SM00002			S	YC051-YD158, YL951-YR328
5546	20		CQ		9-3	31-52-71	D40824P		15		SM00002			S	YC051-YD158, YL951-YR328
5547	20		CQ		3-10	31-52-71	D40822P		19		SM00002			S	YC051-YD158, YL951-YR328
5548	20		CQ		9-0	31-52-75	D01346		17		D46104P		25		YC051-YD158, YL951-YR328
5549	20		CQ		15-6	31-52-75	D40824P		9		D46104P		26		YC051-YD158, YL951-YR328
5550	20		PA		4-9	21-33-11	D00776		B		GD00800	DC..	1A		YC051-YC059, YC065-YD158, YL951, YN231
5550	20		CQ		5-0	21-33-11	D00776		B		GD00800	DC..	1A		YC060-YC064
5550	20		CQ		4-9	21-33-11	D00776		B		GD00800	DC..	1A		YL952-YL999, YN232-YR328
5551	22		PA		15-5	21-33-11	D00940		3		D46104P		2		YC051-YC059, YC065-YD158, YL951, YN231
5551	22		CQ		16-8	21-33-11	D00940		3		D46104P		2		YC060-YC064
5551	22		CQ		15-5	21-33-11	D00940		3		D46104P		2		YL952-YL999, YN232-YR328
5552	22		PA		15-1	21-33-11	D00776		A		D46104P		3		YC051-YC059, YC065-YD158, YL951, YN231
5552	22		CQ		16-8	21-33-11	D00776		A		D46104P		3		YC060-YC064
5552	22		CQ		15-1	21-33-11	D00776		A		D46104P		3		YL952-YL999, YN232-YR328
5553	22		CQ		10-1	34-16-21	D00940		11		D40822P		16		YC051-YD158, YL951-YR328
5554	22		CQ		18-5	34-16-21	D00940		10		D40826J		26		YC051-YD158, YL951-YR328
5555	22		PA		10-5	34-16-11	D01172		1		D40830P		14		YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5510

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5514	286A5514			FLIGHT DECK PANEL LIGHTING (SA2) (continued)											
5556	22		PA		18-7	34-16-11	D01172		2		D40826J		24		YC051-YD158, YL951-YR328
5557	22		PA		15-4	23-42-11	D00940		7		TB0606X	A003	1A		YC051-YD157
5557	22		PA		15-4	23-42-11	D00940		7		TB0608Z	A005	1A		YD158, YL951-YR328
5558	22		CQ		18-5	23-22-11	D00940		8		D40826J		9		YC051-YD158, YL951-YR328
5559	20		CQ		10-6	31-52-71	D40822P		18		D46104P		24		YC051-YD158, YL951-YR328
5561	20		CQ		11-4	33-18-62	D40822P		20		TB0804Z	A017	1A		YC051-YC053
5561	20		CQ		11-4	33-18-62	D40822P		20		TB0804Z	B021	1A		YC054-YD158, YL951-YR328
5562	20		CQ		9-0	22-11-12	D01344		7		TB0805Y	A009	1A		YC051-YD158, YL951-YR328
5563	20		CQ		9-1	22-11-12	D02866		47		TB0805Y	B009	1A		YC051-YD158, YL951-YR328
5564	20		PA		18-6	SPARE	D40824P		19		D40826J		6		YC051-YD158, YL951-YR328
5565	20		PA		18-6	SPARE	D40824P		20		D40826J		8		YC051-YD158, YL951-YR328
5568	20		GA		13-7	SPARE	D40822P		23		D40826J		10		YC051-YD154
5568	20		PA		13-7	SPARE	D40822P		23		D40826J		10		YD155-YD157
5569	20		GA		13-7	SPARE	D40822P		24		D40826J		11		YC051-YD154
5569	20		PA		13-7	SPARE	D40822P		24		D40826J		11		YD155-YD157
5570	20		PA		11-0	SPARE	D40824P		32		D40830P		1		YC051-YD158, YL951-YR328
5571	20		PA		11-0	SPARE	D40824P		33		D40830P		2		YC051-YD158, YL951-YR328
5572	20		PA		25-10	SPARE	D40826J		12		D40830P		3		YC051-YD158, YL951-YR328
5573	20		PA		25-10	SPARE	D40826J		13		D40830P		4		YC051-YD158, YL951-YR328
5574	20		PA		3-7	31-51-11	D00940		15		GD0911B	ST..	1A		YC051-YD158, YL951-YR328
5576	20		GA		11-0	33-18-62	TB0801X	B002	1A		D40822P		4		YC051-YC052
5576	20		PA		11-4	33-18-62	TB0804Y	A007	1A		D40822P		4		YC053-YD158, YL951-YR328
5577	20		CQ		11-0	33-18-62	TB0801X	A003	1A		D40822P		14		YC051-YD157
5577	20		CQ		11-4	33-18-62	TB0804Y	B005	1A		D40822P		14		YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W5510

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5514	286A5514				FLIGHT DECK PANEL LIGHTING (SA2) (continued)										
5578	22		PA		10-6	31-53-11	D40822P		6		D46104P	27			YC051-YD158, YL951-YR328
5580	22		PA		15-0	32-44-11	D40822P		12		S00100	1NO	B	*	YC051-YD157
5582	20		CQ		7-3	31-52-11	D46104P		4		SM00008		S		YC051-YD158, YL951-YR328
5585	20		CQ		0-7	33-18-62	TB0804Z	A017	1A		TB0804Z	B021	1A		YC054-YD158
5585	20		CQ		0-7	33-18-62	TB0804Z	B021	1A		TB0804Z	A017	1A		YL951-YR328
5586	20		CQ		11-0	33-18-61	D40822P		8		TB0803Y	A009	1A		YD155-YD158, YL951-YR328
5590	20		CQ		0-7	33-18-61	TB0803Y	A009	1A		TB0803Y	A013	1A		YD155-YD158, YL951-YR328
5591	20		PA		10-6	28-23-11	D40822P		15		TB0608X	A002	1A		YD158, YL951-YR328
5592	20		PA		10-6	28-23-11	D40822P		23		TB0608X	B002	1A		YD158, YL951-YR328
5593	20		PA		10-6	28-23-11	D40822P		24		TB0608X	A004	1A		YD158, YL951-YR328
5594	16		PA		25-10	47-30-11	D40830P		13		D40826J	10	16		YL951-YR328
5601	22		CQ		20-0	21-33-11	SP00575				D40824P	39			YC060-YC064
5601	22		PA		15-6	21-33-11	D40824P		39		D46104P	CAP	Y		YL951-YL952, YN231-YN232
5601	22		PA		15-6	21-33-11	D40824P		39		D46104P	39			YL953-YL999, YN233-YR328
5602	22		CQ		37-6	31-53-11	SP00795			W	D40824P	10			YC060-YC064
5602	22		PA		15-6	31-53-11	D40824P		10		D46104P	CAP	Y		YL951-YL952, YN231-YN232
5602	22		PA		15-6	31-53-11	D40824P		10		D46104P	38			YL953-YL999, YN233-YR328
5603	22		CQ		25-0	31-53-11	SP00573			W	TB0501Y	B015	1A		YC060-YC064
5781	22		PA		2-2	32-44-11	S00100		2C	B	GD00298	DC..	E		YC051-YD158, YL951-YR328
5782	22		CQ		20-0	32-44-11	S00100		2NC	B	D40824P	38			YC051-YD158, YL951-YR328
5783	22		PA		19-11	32-44-11	S00100		2NO	B	D40824P	27			YC051-YD158, YL951-YL999, YR301-YR328
5783	22		CQ		19-11	32-44-11	S00100		2NO	B	D40824P	27			YN231-YN501
5784	24		B6		10-6	21-27-31	D40822P		17		D46104P	1			YC051-YD158, YL951-YR328
5786	18		CQ		22-10	33-45-11	D40830P		12		D46104P	23			YL951-YR328
6001R	22		PH		12-0	26-11-21	D01344		3		D40826J	20			YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11
Section W5510
Page 10
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W5514	286A5514				FLIGHT DECK PANEL LIGHTING (SA2) (continued)										
6002R	22		PH		18-5	26-11-21	D00940		13		D40826J		22		YC051-YD158, YL951-YR328
6003R	22		PH		18-5	26-11-21	D00940		12		D40826J		21		YC051-YD158, YL951-YR328

For training purposes only!

WIRE LIST

D280A108

91-21-11

Section W5510

Page 11 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		Diagram	From			To					
	Wire No.	GA	CO TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5526	286A5526				DISC AB0500DL TO E1-4, E4-1 (SA2)											
0301	24		PK		45-0	21-51-15		D43018P	A09			D04580P	6			YC051-YC055
0301	24		PK		44-11	21-51-15		D43018P	A09			D04580P	6			YC056-YD158
0301	24		PK		44-9	21-51-15		D43018P	A09			D04580P	6			YD160-YL999, YR301-YR328
0501	20		PA		31-10	47-30-11		D43018P	B09			D43016J	11			YD160-YR328
0511	24		PK		47-1	32-44-11		D43016J	1			D40302J	1			YC051-YC055
0511	24		PK		46-10	32-44-11		D43016J	1			D40302J	1			YC056-YD158
0511	24		PK		47-3	32-44-11		D43016J	1			D40302J	1			YD160-YL999, YR301-YR328
0511	24		PK		37-6	32-44-11		D43016J	1			D40302J	1			YN231-YN501
0513	24		PK		47-1	32-44-11		D43016J	2			D40302J	2			YC051-YC055
0513	24		PK		46-10	32-44-11		D43016J	2			D40302J	2			YC056-YD158
0513	24		PK		47-3	32-44-11		D43016J	2			D40302J	2			YD160-YL999, YR301-YR328
0513	24		PK		37-6	32-44-11		D43016J	2			D40302J	2			YN231-YN501
0514	24		PK		47-1	32-44-11		D43016J	3			D40302J	3			YC051-YC055
0514	24		PK		46-10	32-44-11		D43016J	3			D40302J	3			YC056-YD158
0514	24		PK		47-3	32-44-11		D43016J	3			D40302J	3			YD160-YL999, YR301-YR328
0514	24		PK		37-6	32-44-11		D43016J	3			D40302J	3			YN231-YN501
0516	24		PK		47-1	32-44-11		D43016J	4			D40302J	4			YC051-YC055
0516	24		PK		46-10	32-44-11		D43016J	4			D40302J	4			YC056-YD158
0516	24		PK		47-3	32-44-11		D43016J	4			D40302J	4			YD160-YL999, YR301-YR328
0516	24		PK		37-6	32-44-11		D43016J	4			D40302J	4			YN231-YN501
0517	24		PK		47-1	32-44-11		D43016J	5			D40302J	5			YC051-YC055
0517	24		PK		46-10	32-44-11		D43016J	5			D40302J	5			YC056-YD158
0517	24		PK		47-3	32-44-11		D43016J	5			D40302J	5			YD160-YL999, YR301-YR328
0517	24		PK		37-6	32-44-11		D43016J	5			D40302J	5			YN231-YN501
0518	20		PA		5-4	33-33-11		D41502	15			D04580P	2			YC051-YD158
0518	20		PA		5-5	33-33-11		D41502	15			D04580P	2			YD160-YL999, YR301-YR328
0518	20		PA		6-1	33-33-11		D41502	15			D04580P	2			YN231-YN501
0519	20		PA		5-4	33-33-11		D41502	16			D04580P	1			YC051-YD158
0519	20		PA		5-5	33-33-11		D41502	16			D04580P	1			YD160-YL999, YR301-YR328
0519	20		PA		6-1	33-33-11		D41502	16			D04580P	1			YN231-YN501
0520	20		PA		7-2	33-33-11		SP00418		9		D04580P	4			YC051-YD158

WIRE LIST

D280A108

91-21-11

Section W5520

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5526 286A5526 DISC AB0500DL TO E1-4, E4-1 (SA2) (continued)																
0520		20		PA		7-8	33-33-11	SP00418			9	D04580P		4		YD160-YL999, YR301-YR328
0520		20		PA		8-0	33-33-11	SP00418			9	D04580P		4		YN231-YN501
0521		20		PA		7-2	33-33-11	SP00420			9	D04580P		3		YC051-YD158
0521		20		PA		7-8	33-33-11	SP00420			9	D04580P		3		YD160-YL999, YR301-YR328
0521		20		PA		8-0	33-33-11	SP00420			9	D04580P		3		YN231-YN501
0591		22		PA		47-1	32-41-11	D43016J		6		D40302J		6		YC051-YC055
0591		22		PA		46-10	32-41-11	D43016J		6		D40302J		6		YC056-YD158
0591		22		PA		47-3	32-41-11	D43016J		6		D40302J		6		YD160-YL999, YR301-YR328
0591		22		PA		37-6	32-41-11	D43016J		6		D40302J		6		YN231-YN501
5501		24		PK		45-2	21-51-11	D43018P		A01		D41502		1		YC051-YD158
5501		24		PK		45-0	21-51-11	D43018P		A01		D41502		1		YD160-YL999, YR301-YR328
5501		24		PK		34-2	21-51-11	D43018P		A01		D41502		1		YN231-YN501
5502		24		PK		45-2	21-51-11	D43018P		A02		D41502		2		YC051-YD158
5502		24		PK		45-0	21-51-11	D43018P		A02		D41502		2		YD160-YL999, YR301-YR328
5502		24		PK		34-2	21-51-11	D43018P		A02		D41502		2		YN231-YN501
5503		24		PK		45-2	21-51-11	D43018P		A03		D41502		3		YC051-YD158
5503		24		PK		45-0	21-51-11	D43018P		A03		D41502		3		YD160-YL999, YR301-YR328
5503		24		PK		34-2	21-51-11	D43018P		A03		D41502		3		YN231-YN501
5504		24		PK		45-2	21-51-11	D43018P		A04		D41502		4		YC051-YD158
5504		24		PK		45-0	21-51-11	D43018P		A04		D41502		4		YD160-YL999, YR301-YR328
5504		24		PK		34-2	21-51-11	D43018P		A04		D41502		4		YN231-YN501
5505		24		PK		45-2	21-51-11	D43018P		A05		D41502		5		YC051-YD158
5505		24		PK		45-0	21-51-11	D43018P		A05		D41502		5		YD160-YL999, YR301-YR328
5505		24		PK		34-2	21-51-11	D43018P		A05		D41502		5		YN231-YN501
5506		24		PK		45-2	21-51-11	D43018P		A06		D41502		6		YC051-YD158
5506		24		PK		45-0	21-51-11	D43018P		A06		D41502		6		YD160-YL999, YR301-YR328
5506		24		PK		34-2	21-51-11	D43018P		A06		D41502		6		YN231-YN501
5507		22		PA		45-2	21-42-11	D43018P		A07		D41502		8		YC051-YD158
5507		22		PA		45-0	21-42-11	D43018P		A07		D41502		8		YD160-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W5520

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To				Effectivity		
Wire No.	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W5526	286A5526				DISC AB0500DL TO E1-4, E4-1 (SA2) (continued)												
5507	22		PA		34-2	21-42-11	D43018P	A07			D41502	8			YN231-YN501		
5508	24		PK		45-0	21-51-15	D43018P	A08			D04580P	7			YC051-YC055		
5508	24		PK		44-11	21-51-15	D43018P	A08			D04580P	7			YC056-YD158		
5508	24		PK		44-9	21-51-15	D43018P	A08			D04580P	7			YD160-YL999, YR301-YR328		
5508	24		PK		34-4	21-51-15	D43018P	A08			D04580P	7			YN231-YN501		
5509	20		PA		19-4	21-51-15	D43018P	A09			D00534	2			YN231-YN501		
5510	20		PA		13-4	21-51-15	D00534	1			GD00422	DC..	E		YN231-YN501		
5512	20		PA		56-11	SPARE	D04580P	12			D43016J	7			YC051-YC055, YD160-YL999, YR301-YR328		
5512	20		PA		56-9	SPARE	D04580P	12			D43016J	7			YC056-YD158		
5512	20		PA		46-0	SPARE	D04580P	12			D43016J	7			YN231-YN501		
5513	20		PA		56-11	SPARE	D04580P	13			D43016J	8			YC051-YC055, YD160-YL999, YR301-YR328		
5513	20		PA		56-9	SPARE	D04580P	13			D43016J	8			YC056-YD158		
5513	20		PA		46-0	SPARE	D04580P	13			D43016J	8			YN231-YN501		
5516	20		PA		47-1	SPARE	D40302J	10			D43016J	9			YC051-YC055		
5516	20		PA		46-10	SPARE	D40302J	10			D43016J	9			YC056-YD158		
5516	20		PA		47-3	SPARE	D40302J	10			D43016J	9			YD160-YL999, YR301-YR328		
5516	20		PA		37-6	SPARE	D40302J	10			D43016J	9			YN231-YN501		
5517	20		PA		47-1	SPARE	D40302J	11			D43016J	10			YC051-YC055		
5517	20		PA		46-10	SPARE	D40302J	11			D43016J	10			YC056-YD158		
5517	20		PA		47-3	SPARE	D40302J	11			D43016J	10			YD160-YL999, YR301-YR328		
5517	20		PA		37-6	SPARE	D40302J	11			D43016J	10			YN231-YN501		
5518	24		PK		45-2	36-11-11	D43018P	B01			D41502	9			YC051-YD158		
5518	24		PK		45-0	36-11-11	D43018P	B01			D41502	9			YD160-YL999, YR301-YR328		
5518	24		PK		34-2	36-11-11	D43018P	B01			D41502	9			YN231-YN501		
5519	24		PK		45-2	36-11-11	D43018P	B02			D41502	10			YC051-YD158		
5519	24		PK		45-0	36-11-11	D43018P	B02			D41502	10			YD160-YL999, YR301-YR328		
5519	24		PK		34-2	36-11-11	D43018P	B02			D41502	10			YN231-YN501		
5520	24		PK		45-2	36-11-11	D43018P	B03			D41502	11			YC051-YD158		
5520	24		PK		45-0	36-11-11	D43018P	B03			D41502	11			YD160-YL999, YR301-YR328		

WIRE LIST

D280A108

91-21-11

Section W5520

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W5526	286A5526				DISC AB0500DL TO E1-4, E4-1 (SA2) (continued)												
5520	24		PK		34-2	36-11-11		D43018P	B03			D41502	11			YN231-YN501	
5521	24		PK		45-2	36-11-11		D43018P	B04			D41502	12			YC051-YD158	
5521	24		PK		45-0	36-11-11		D43018P	B04			D41502	12			YD160-YL999, YR301-YR328	
5521	24		PK		34-2	36-11-11		D43018P	B04			D41502	12			YN231-YN501	
5522	22		PA		45-2	34-61-17		D43018P	B05			D41502	13			YC051-YD158	
5522	22		PA		45-0	34-61-17		D43018P	B05			D41502	13			YD160-YL999, YR301-YR328	
5522	22		PA		34-2	34-61-17		D43018P	B05			D41502	13			YN231-YN501	
5523	20		PA		44-5	21-51-15		D43018P	A10			D03940	2			YC051-YC055	
5523	20		PA		44-4	21-51-15		D43018P	A10			D03940	2			YC056-YD158	
5523	20		PA		44-3	21-51-15		D43018P	A10			D03940	2			YD160-YL999, YR301-YR328	
5523	24		PK		34-4	21-51-15		D43018P	A10			D04580P	5			YN231-YN501	
5524	24		PK		45-2	21-61-11		D43018P	B06			D41502	17			YC051-YD158	
5524	24		PK		45-0	21-61-11		D43018P	B06			D41502	17			YD160-YL999, YR301-YR328	
5525	24		PK		45-2	21-61-11		D43018P	B07			D41502	18			YC051-YD158	
5525	24		PK		45-0	21-61-11		D43018P	B07			D41502	18			YD160-YL999, YR301-YR328	
5526	24		PK		45-2	21-61-11		D43018P	B08			D41502	19			YC051-YD158	
5526	24		PK		45-0	21-61-11		D43018P	B08			D41502	19			YD160-YL999, YR301-YR328	
5527	24		PK		42-3	21-61-11		D41842P	A01			D41502	20			YC051-YC055	
5527	24		PK		42-4	21-61-11		D41842P	A01			D41502	20			YC056-YD158	
5527	24		PK		42-6	21-61-11		D41842P	A01			D41502	20			YD160-YL999, YR301-YR328	
5528	24		PK		42-3	21-61-11		D41842P	A02			D41502	21			YC051-YC055	
5528	24		PK		42-4	21-61-11		D41842P	A02			D41502	21			YC056-YD158	
5528	24		PK		42-6	21-61-11		D41842P	A02			D41502	21			YD160-YL999, YR301-YR328	
5529	24		PK		42-3	21-61-11		D41842P	A03			D41502	22			YC051-YC055	
5529	24		PK		42-4	21-61-11		D41842P	A03			D41502	22			YC056-YD158	
5529	24		PK		42-6	21-61-11		D41842P	A03			D41502	22			YD160-YL999, YR301-YR328	
5530	20		PA		47-1	29-11-11		D43016J	15			D40302J	13			YC051-YC055	
5530	20		PA		46-10	29-11-11		D43016J	15			D40302J	13			YC056-YD158	
5530	20		PA		47-3	29-11-11		D43016J	15			D40302J	13			YD160-YL999, YR301-YR328	

WIRE LIST

D280A108

91-21-11

Section W5520

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description	Diagram	From				To				Effectivity	
Wire No.	GA	CO	TY		FT-IN		Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W5526	286A5526				DISC AB0500DL TO E1-4, E4-1 (SA2) (continued)											
5530	20		PA		37-6	29-11-11	D43016J				D40302J		13		YN231-YN501	
5531	20		PA		47-1	29-11-11	D43016J				D40302J		14		YC051-YC055	
5531	20		PA		46-10	29-11-11	D43016J				D40302J		14		YC056-YD158	
5531	20		PA		47-3	29-11-11	D43016J				D40302J		14		YD160-YL999, YR301-YR328	
5531	20		PA		37-6	29-11-11	D43016J				D40302J		14		YN231-YN501	
5532	20		PA		9-8	21-51-15	D03940				GD00068	DC..	1		YC051-YD158	
5532	20		PA		9-5	21-51-15	D03940				GD00068	DC..	1		YD160-YL999, YR301-YR328	
6001R	20		PH		47-1	26-12-11	D40302J				D43016J		17		YC051-YC055	
6001R	20		PH		46-10	26-12-11	D40302J				D43016J		17		YC056-YD158	
6001R	20		PH		47-3	26-12-11	D40302J				D43016J		17		YD160-YL999, YR301-YR328	
6001R	20		PH		37-6	26-12-11	D40302J				D43016J		17		YN231-YN501	
6002R	20		PH		56-11	26-12-11	D43016J				D04580P		8		YC051-YC055, YD160-YL999, YR301-YR328	
6002R	20		PH		56-9	26-12-11	D43016J				D04580P		8		YC056-YD158	
6002R	20		PH		46-0	26-12-11	D43016J				D04580P		8		YN231-YN501	
6003R	20		PH		56-11	26-12-11	D43016J				D04580P		9		YC051-YC055, YD160-YL999, YR301-YR328	
6003R	20		PH		56-9	26-12-11	D43016J				D04580P		9		YC056-YD158	
6003R	20		PH		46-0	26-12-11	D43016J				D04580P		9		YN231-YN501	
6004R	20		PH		56-11	26-12-11	D43016J				D04580P		10		YC051-YC055, YD160-YL999, YR301-YR328	
6004R	20		PH		56-9	26-12-11	D43016J				D04580P		10		YC056-YD158	
6004R	20		PH		46-0	26-12-11	D43016J				D04580P		10		YN231-YN501	
6005R	20		PH		5-4	26-12-11	D04580P				D41502		14		YC051-YD158	
6005R	20		PH		5-5	26-12-11	D04580P				D41502		14		YD160-YL999, YR301-YR328	
6005R	20		PH		6-1	26-12-11	D04580P				D41502		14		YN231-YN501	

WIRE LIST

D280A108

91-21-11

Section W5520

Page 5 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W5530	286A5530				DISC AB0500DL TO E3-2										
0030	22		CQ		31-8	31-31-15	D40318J	24			D43022P	A03		YC065-YL999, YR301-YR328	
0030	22		CQ		21-11	31-31-15	D40318J	24			D43022P	A03		YN231-YN501	
0511	22		GK		50-5	29-32-11	D43022P	A12			D46028J	2		YC051-YL999, YR301-YR328	
0511	22		GK		40-5	29-32-11	D43022P	A12			D46028J	2		YN231-YN501	
0512	22		GK		50-5	29-32-11	D43022P	B12			D46028J	1		YC051-YL999, YR301-YR328	
0512	22		GK		40-5	29-32-11	D43022P	B12			D46028J	1		YN231-YN501	
0517	22		PA		31-8	29-33-11	D43022P	A19			D40318J	16		YC051-YL999, YR301-YR328	
0517	22		PA		21-6	29-33-11	D43022P	A19			D40318J	16		YN231-YN501	
0518	22		PA		31-8	29-33-11	D43022P	B19			D40318J	15		YC051-YL999, YR301-YR328	
0518	22		PA		21-6	29-33-11	D43022P	B19			D40318J	15		YN231-YN501	
1101	22		X1	BN	31-8	31-62-14	D43022P	A17			D40318J	23		YC051-YL999, YR301-YR328	
1101	22		X1	BN	21-6	31-62-14	D43022P	A17			D40318J	23		YN231-YN501	
1101Z				BN	0-0	31-62-14	D43022P	PERG	1F		D40318J	DED		ALL	
1102R	20		X5	BP	31-8	26-12-11	D43022P	B03			D40318J	18		YC051-YL999, YR301-YR328	
1102R	20		X5	BP	21-11	26-12-11	D43022P	B03			D40318J	18		YN231-YN501	
1102Z				BP	0-0	26-12-11	D43022P	DED			D40318J	DED		ALL	
2211B	20		X2	KK	50-5	32-41-11	D43022P	B01			D46028J	7		YC051-YL999, YR301-YR328	
2211B	20		X2	KK	40-5	32-41-11	D43022P	B01			D46028J	7		YN231-YN501	
2211R	20		X2	KK	0-0	32-41-11	D43022P	A01			D46028J	6		ALL	
2211Z				KK	0-0	32-41-11	D43022P	A02			D46028J	8		ALL	
2221B	22		GL	KV	50-5	32-64-11	D43022P	B10			D46028J	10		YC051-YL999, YR301-YR328	
2221B	22		GL	KV	40-5	32-64-11	D43022P	B10			D46028J	10		YN231-YN501	
2221R	22		GL	KV	0-0	32-64-11	D43022P	A10			D46028J	9		ALL	
2222B	22		GL	KW	50-5	32-64-11	D43022P	A11			D46028J	5		YC051-YL999, YR301-YR328	
2222B	22		GL	KW	40-5	32-64-11	D43022P	A11			D46028J	5		YN231-YN501	
2222R	22		GL	KW	0-0	32-64-11	D43022P	B11			D46028J	4		ALL	
2232B	22		GL	LG	50-5	32-31-11	D43022P	B09			D46028J	13		YC051-YL999, YR301-YR328	
2232B	22		GL	LG	40-5	32-31-11	D43022P	B09			D46028J	13		YN231-YN501	

WIRE LIST

D280A108

91-21-11

Section W5530

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5530	286A5530				DISC AB0500DL TO E3-2 (continued)										
2232R	22	GL	LG		0-0	32-31-11	D43022P	A09			D46028J	12			ALL
2601B	22	PB	SA		31-8	78-36-11	D43022P	B06			D40318J	20			YC051-YL999, YR301-YR328
2601B	22	PB	SA		21-11	78-36-11	D43022P	B06			D40318J	20			YN231-YN501
2601R	22	PB	SA		0-0	78-36-11	D43022P	A07			D40318J	19			ALL
2602B	22	PB	SB		31-8	78-36-11	D43022P	B07			D40318J	22			YC051-YL999, YR301-YR328
2602B	22	PB	SB		21-11	78-36-11	D43022P	B07			D40318J	22			YN231-YN501
2602R	22	PB	SB		0-0	78-36-11	D43022P	A08			D40318J	21			ALL
6001	20	CQ			31-8	78-34-11	D43022P	A04			D40318J	17			YC051-YL999, YR301-YR328
6001	20	CQ			21-11	78-34-11	D43022P	A04			D40318J	17			YN231-YN501
6002	20	CQ			31-8	78-34-11	D43022P	B04			D40318J	9			YC051-YL999, YR301-YR328
6002	20	CQ			21-11	78-34-11	D43022P	B04			D40318J	9			YN231-YN501
6003	20	CQ			31-8	78-34-11	D43022P	A05			D40318J	10			YC051-YL999, YR301-YR328
6003	20	CQ			21-11	78-34-11	D43022P	A05			D40318J	10			YN231-YN501
6004	20	CQ			31-8	78-34-11	D43022P	B05			D40318J	8			YC051-YL999, YR301-YR328
6004	20	CQ			21-11	78-34-11	D43022P	B05			D40318J	8			YN231-YN501
6005	20	CQ			31-8	78-34-11	D43022P	A06			D40318J	7			YC051-YL999, YR301-YR328
6005	20	CQ			21-11	78-34-11	D43022P	A06			D40318J	7			YN231-YN501
6007	20	CQ			50-5	28-42-11	D43022P	A13			D46028J	16			YC051-YL999, YR301-YR328
6007	20	CQ			40-5	28-42-11	D43022P	A13			D46028J	16			YN231-YN501
6008	20	CQ			50-5	28-42-11	D43022P	B13			D46028J	15			YC051-YL999, YR301-YR328
6008	20	CQ			40-5	28-42-11	D43022P	B13			D46028J	15			YN231-YN501
6011	20	CQ			10-8	28-21-11	SP00358		S		D46028J	3			ALL

WIRE LIST

D280A108

91-21-11
Section W5530
Page 2 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Fam	Diagram	From				To				Effectivity
	Wire No.	GA	CO TY				Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W5562	286A5562			WING BODY PRESS SEAL TO RADAR BAY											
1301	20	C2	EN	50-0	28-41-11	D39913		17			D11304		8		YC051-YC055
1301	20	C2	EN	49-11	28-41-11	D39913		17			D11304		8		YC056-YL999, YR301-YR328
1301	20	C2	EN	39-5	28-41-11	D39913		17			D11304		8		YN231
1301	20	C2	EN	39-9	28-41-11	D39913		17			D11304		8		YN232-YN501
1301ZI			EN	0-0	28-41-11	D39913				FC	D11304			FA	ALL
1301ZO			EN	0-0	28-41-11	D39913		S/R			D11304		S/R		ALL
1302	20	C1	EP	50-0	28-41-11	D39913		21			D11304		23		YC051-YC055
1302	20	C1	EP	49-11	28-41-11	D39913		21			D11304		23		YC056-YL999, YR301-YR328
1302	20	C1	EP	39-5	28-41-11	D39913		21			D11304		23		YN231
1302	20	C1	EP	39-9	28-41-11	D39913		21			D11304		23		YN232-YN501
1302Z			EP	0-0	28-41-11	D39913		S/R			D11304		S/R		ALL
1303	20	C1	EQ	50-0	28-41-11	D39913		20			D11304		22		YC051-YC055
1303	20	C1	EQ	49-11	28-41-11	D39913		20			D11304		22		YC056-YL999, YR301-YR328
1303	20	C1	EQ	39-9	28-41-11	D39913		20			D11304		22		YN231-YN501
1303Z			EQ	0-0	28-41-11	D39913		S/R			D11304		S/R		ALL
2601B	22	X2	SA	11-3	28-41-11	D11304		24			TB1806X	A006	1A		ALL
2601R	22	X2	SA	0-0	28-41-11	D11304		25			TB1806X	A005	1A		ALL
2601Z			SA	0-0	28-41-11	D11304		S/R			GB01806	ST..	1A		ALL
6001	22	PA		1-3	28-41-11	D11304		2			D11304	CAP	Y		YC051-YC055
6001	22	PA		0-7	28-41-11	D11304		2			D11304	CAP	Y		YC056-YR328
6002	22	PA		1-3	28-41-11	D11304		7			D11304	CAP	Y		YC051-YC055
6002	22	PA		0-7	28-41-11	D11304		7			D11304	CAP	Y		YC056-YR328
6003	22	PA		1-3	28-41-11	D11304		20			D11304	CAP	Y		YC051-YC055
6003	22	PA		0-7	28-41-11	D11304		20			D11304	CAP	Y		YC056-YR328
6004	22	PA		1-3	28-41-11	D11304		21			D11304	CAP	Y		YC051-YC055
6004	22	PA		0-7	28-41-11	D11304		21			D11304	CAP	Y		YC056-YR328
6005	22	PA		11-3	28-41-11	TB1806X	B005	1A			D11352		1		ALL
6006	22	PA		1-11	28-41-11	D11304		1			GD01000	ST..	E		ALL
6007	20	PA		2-0	28-41-11	D11352		2			GD00022	DC..	E		ALL
6009	20	PA		0-7	28-41-11	D39913		38			D39913	S/R			ALL
6010	20	PA		0-7	28-41-11	D39913		39			D39913		7		ALL
6011	20	PA		0-7	28-41-11	D39913		6			D39913		16		ALL
FRAA				0-0	28-41-11	D11304		9			D11304			FA	ALL
FRAB				0-0	28-41-11	D11304		19			D11304			FA	ALL
FRAC				0-0	28-41-11	D39913		18			D39913			FC	ALL
FRAD				0-0	28-41-11	D39913		37			D39913			FC	ALL

WIRE LIST

D280A108

91-21-11

Section W5560

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5564	286A5564				WING BODY PRESS SEAL TO E/E BAY										
2601B	20	X2	SA		36-3	SPARE	D39909	6			D40136P	A01			YC051-YC055
2601B	20	X2	SA		36-1	SPARE	D39909	6			D40136P	A01			YC056-YL999, YR301-YR328
2601B	20	X2	SA		25-5	SPARE	D39909	6			D40136P	A01			YN231-YN501
2601R	20	X2	SA		0-0	SPARE	D39909	5			D40136P	B01			ALL
2601Z			SA		0-0	SPARE	D39909	S/R			D40136P	PERG	1F		ALL
2602B	24	Y2	SB		36-3	77-12-21	D39909	3			D40136P	A08			YC051-YC055
2602B	24	Y2	SB		36-1	77-12-21	D39909	3			D40136P	A08			YC056-YL999, YR301-YR328
2602B	24	Y2	SB		25-5	77-12-21	D39909	3			D40136P	A08			YN231-YN501
2602R	24	Y2	SB		0-0	77-12-21	D39909	4			D40136P	B08			ALL
2602Z			SB		0-0	77-12-21	D39909	S/R			D40136P	PERG	1F		ALL
2603B	24	PL	SC		36-3	76-21-11	D39909	8			D40136P	A03			YC051-YC055
2603B	24	PL	SC		36-1	76-21-11	D39909	8			D40136P	A03			YC056-YL999, YR301-YR328
2603B	24	PL	SC		25-5	76-21-11	D39909	8			D40136P	A03			YN231-YN501
2603R	24	PL	SC		0-0	76-21-11	D39909	9			D40136P	B03			ALL
6001	20	PA			36-3	80-11-11	D39909	7			D40136P	A04			YC051-YC055
6001	20	PA			36-1	80-11-11	D39909	7			D40136P	A04			YC056-YL999, YR301-YR328
6001	20	PA			25-5	80-11-11	D39909	7			D40136P	A04			YN231-YN501
6002	24	PK			36-3	80-11-11	D39909	11			D40136P	B04			YC051-YC055
6002	24	PK			36-1	80-11-11	D39909	11			D40136P	B04			YC056-YL999, YR301-YR328
6002	24	PK			25-5	80-11-11	D39909	11			D40136P	B04			YN231-YN501
6003	20	PA			36-3	76-21-11	D39909	10			D40136P	A05			YC051-YC055
6003	20	PA			36-1	76-21-11	D39909	10			D40136P	A05			YC056-YL999, YR301-YR328
6003	20	PA			25-5	76-21-11	D39909	10			D40136P	A05			YN231-YN501
W5566	286A5566				P18 LEFT CAB CEILING TO WING/BODY DISCBUNDLE A										
0001	16	PA			35-11	33-45-11	D39905	12			D40118P	4			YC051-YC055
0001	16	PA			36-5	33-45-11	D39905	12			D40118P	4			YC056-YD153
0001	16	PA			36-5	33-45-11	D39905	7			D40118P	4			YD154-YL999, YR301-YR328
0001	16	PA			26-4	33-45-11	D39905	7			D40118P	4			YN231-YN501
0002	20	PA			35-11	33-44-12	D39905	11			D40118P	1			YC051-YC055
0002	20	PA			36-5	33-44-12	D39905	11			D40118P	1			YC056-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W5560

Page 2

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type
W5566	286A5566				P18 LEFT CAB CEILING TO WING/BODY DISCBUNDLE A (continued)										
0002	20		PA		26-4	33-44-12	D39905		11		D40118P		1		YN231-YN501
0003	18		PA		35-11	33-42-11	D39905		14		D40118P		7		YC051-YC055
0003	18		PA		36-5	33-42-11	D39905		14		D40118P		7		YC056-YL999, YR301-YR328
0003	18		PA		26-4	33-42-11	D39905		14		D40118P		7		YN231-YN501
0004	20		PA		35-11	33-43-11	D39905		18		D40118P		2		YC051-YC055
0004	20		PA		36-5	33-43-11	D39905		18		D40118P		2		YC056-YL999, YR301-YR328
0004	20		PA		26-4	33-43-11	D39905		18		D40118P		2		YN231-YN501
2601B	20		PB	SA	18-11	28-44-11	D39905		21		TB0205W	B009	1		YC051-YC055
2601B	20		PB	SA	19-0	28-44-11	D39905		21		TB0205W	B009	1		YC056-YL999, YR301-YR328
2601B	20		PB	SA	18-5	28-44-11	D39905		21		TB0205W	B009	1		YN231-YN501
2601R	20		PB	SA	0-0	28-44-11	D39905		20		TB0205V	B015	1		ALL
6001	22		PA		35-11	28-43-11	D39905		9		D40118P		3		YC051-YC055
6001	22		PA		36-5	28-43-11	D39905		9		D40118P		3		YC056-YL999, YR301-YR328
6001	22		PA		26-4	28-43-11	D39905		9		D40118P		3		YN231-YN501
6002	22		PA		35-11	30-11-11	D39905		3		D40118P		12		YC051-YC055
6002	22		PA		36-5	30-11-11	D39905		3		D40118P		12		YC056-YL999, YR301-YR328
6002	22		PA		26-4	30-11-11	D39905		3		D40118P		12		YN231-YN501
6003	22		PA		35-11	30-11-11	D39905		5		D40118P		11		YC051-YC055
6003	22		PA		36-5	30-11-11	D39905		5		D40118P		11		YC056-YL999, YR301-YR328
6003	22		PA		26-4	30-11-11	D39905		5		D40118P		11		YN231-YN501
W5568	286A5568				LEFT WING BODY PRESS SEAL TO E/E BAY										
1301	22		X1	EN	29-11	28-43-11	D41852J		1		D40258P		A10		YC051-YC055
1301	22		X1	EN	30-1	28-43-11	D41852J		1		D40258P		A10		YC056-YL999, YR301-YR328
1301	22		X1	EN	20-4	28-43-11	D41852J		1		D40258P		A10		YN231-YN236, YN501
1301Z				EN	0-0	28-43-11	D41852J		DED		D40258P		DED		YC051-YN236, YN501-YR328
1302	22		X1	EP	30-2	28-43-11	D41854J		1		D40258P		A04		YC051-YC055
1302	22		X1	EP	30-4	28-43-11	D41854J		1		D40258P		A04		YC056-YL999, YR301-YR328
1302	22		X1	EP	20-3	28-43-11	D41854J		1		D40258P		A04		YN231-YN236, YN501

WIRE LIST

D280A108

91-21-11

Section W5560

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From				To						
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5568	286A5568			LEFT WING BODY PRESS SEAL TO E/E BAY (continued)											
1302Z				EP	0-0	28-43-11	D41854J	DED			D40258P	DED			YC051-YN236, YN501-YR328
2201B	20	PB	KA		44-8	27-81-11	D39937	4			D40120P	A04			YC051-YD153
2201B	20	PB	KA		44-8	27-81-11	D39937	29			D40120P	A04			YD154-YL999, YR301-YR328
2201B	20	PB	KA		34-11	27-81-11	D39937	29			D40120P	A04			YN231-YN236, YN501
2201R	20	PB	KA		0-0	27-81-11	D39937	13			D40120P	B04			YC051-YN236, YN501-YR328
2202B	20	PB	KB		44-8	27-81-11	D39937	30			D40120P	A05			YC051-YL999, YR301-YR328
2202B	20	PB	KB		34-11	27-81-11	D39937	30			D40120P	A05			YN231-YN236, YN501
2202R	20	PB	KB		0-0	27-81-11	D39937	31			D40120P	B05			YC051-YN236, YN501-YR328
2203B	20	PB	KC		44-8	27-81-11	D39937	32			D40120P	A06			YC051-YL999, YR301-YR328
2203B	20	PB	KC		34-11	27-81-11	D39937	32			D40120P	A06			YN231-YN236, YN501
2203R	20	PB	KC		0-0	27-81-11	D39937	33			D40120P	B06			YC051-YN236, YN501-YR328
2204B	20	PB	KD		44-8	27-81-11	D39937	15			D40120P	A07			YC051-YL999, YR301-YR328
2204B	20	PB	KD		34-11	27-81-11	D39937	15			D40120P	A07			YN231-YN236, YN501
2204R	20	PB	KD		0-0	27-81-11	D39937	34			D40120P	B07			YC051-YN236, YN501-YR328
3601B	20	PC	A4		33-1	28-23-11	D39937	1			D40258P	B03			YC051-YC055
3601B	20	PC	A4		33-3	28-23-11	D39937	1			D40258P	B03			YC056-YL999, YR301-YR328
3601B	20	PC	A4		23-6	28-23-11	D39937	1			D40258P	B03			YN231-YN236, YN501
3601R	20	PC	A4		0-0	28-23-11	D39937	3			D40258P	B01			YC051-YD153
3601R	20	PC	A4		0-0	28-23-11	D39937	9			D40258P	B01			YD154-YN236, YN501-YR328
3601Y	20	PC	A4		0-0	28-23-11	D39937	5			D40258P	B02			YC051-YD153
3601Y	20	PC	A4		0-0	28-23-11	D39937	17			D40258P	B02			YD154-YN236, YN501-YR328
3602B	18	PC	B4		30-1	28-23-11	D05348J	2			D40258P	H			YC051-YC055
3602B	18	PC	B4		30-4	28-23-11	D05348J	2			D40258P	H			YC056-YL999, YR301-YR328
3602B	18	PC	B4		20-6	28-23-11	D05348J	2			D40258P	H			YN231-YN236, YN501
3602R	18	PC	B4		0-0	28-23-11	D05348J	4			D40258P	F			YC051-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W5560

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5568	286A5568			LEFT WING BODY PRESS SEAL TO E/E BAY (continued)											
3602Y	18	PC	B4		0-0	28-23-11	D05348J		3		D40258P		G		YC051-YN236, YN501-YR328
3603B	20	PC	C4		30-2	28-23-11	D05346J		2		D40258P		A03		YC051-YC055
3603B	20	PC	C4		30-4	28-23-11	D05346J		2		D40258P		A03		YC056-YL999, YR301-YR328
3603B	20	PC	C4		20-4	28-23-11	D05346J		2		D40258P		A03		YN231-YN236, YN501
3603R	20	PC	C4		0-0	28-23-11	D05346J		4		D40258P		A01		YC051-YN236, YN501-YR328
3603Y	20	PC	C4		0-0	28-23-11	D05346J		3		D40258P		A02		YC051-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W5560

Page 5 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5580	286A5580				RADAR BAY TO WHEEL WELL DISC STA 675L-CENTER TANK										
1301	20	C2	EN		64-11	28-41-11	D04850J	32			D11308	8			YC051-YC055, YN231
1301	20	C2	EN		64-10	28-41-11	D04850J	32			D11308	8			YC056-YL999, YR301-YR328 YN232-YN501
1301	20	C2	EN		54-10	28-41-11	D04850J	32			D11308	8			YN232-YN501
1301ZI			EN		0-0	28-41-11	D04850J			FC	D11308			FA	ALL
1301ZO			EN		0-0	28-41-11	D04850J		S/R		D11308		S/R		ALL
1302	20	C1	EP		64-11	28-41-11	D04850J	36			D11308	23			YC051-YC055, YN231
1302	20	C1	EP		64-10	28-41-11	D04850J	36			D11308	23			YC056-YL999, YR301-YR328 YN232-YN501
1302	20	C1	EP		54-10	28-41-11	D04850J	36			D11308	23			YN232-YN501
1302Z			EP		0-0	28-41-11	D04850J		S/R		D11308		S/R		ALL
1303	20	C1	EQ		64-11	28-41-11	D04850J	19			D11308	22			YC051-YC055, YN231
1303	20	C1	EQ		64-10	28-41-11	D04850J	19			D11308	22			YC056-YL999, YR301-YR328 YN232-YN501
1303	20	C1	EQ		54-10	28-41-11	D04850J	19			D11308	22			YN232-YN501
1303Z			EQ		0-0	28-41-11	D04850J		S/R		D11308		S/R		ALL
2601B	22	X2	SA		11-1	28-41-11	D11308	24			TB1806X	A008	1A		YC051-YL999, YR301-YR328 YN231
2601B	22	X2	SA		11-4	28-41-11	D11308	24			TB1806X	A008	1A		YN232-YN501
2601B	22	X2	SA		11-2	28-41-11	D11308	24			TB1806X	A008	1A		ALL
2601R	22	X2	SA		0-0	28-41-11	D11308	25			TB1806X	A007	1A		ALL
2601Z			SA		0-0	28-41-11	D11308		S/R		GB01806	ST..	1A		ALL
6001	22	PA			1-4	28-41-11	D11308	2			D11308	CAP	Y		YC051-YC055
6001	22	PA			1-3	28-41-11	D11308	2			D11308	CAP	Y		YC056-YR328
6002	22	PA			1-4	28-41-11	D11308	7			D11308	CAP	Y		YC051-YC055
6002	22	PA			1-3	28-41-11	D11308	7			D11308	CAP	Y		YC056-YR328
6003	22	PA			1-4	28-41-11	D11308	20			D11308	CAP	Y		YC051-YC055
6003	22	PA			1-3	28-41-11	D11308	20			D11308	CAP	Y		YC056-YR328
6004	22	PA			1-4	28-41-11	D11308	21			D11308	CAP	Y		YC051-YC055
6004	22	PA			1-3	28-41-11	D11308	21			D11308	CAP	Y		YC056-YR328
6005	22	PA			0-7	28-41-11	D11308	12			D11308		11		YC051-YD158
6005	22	PA			1-3	28-41-11	D11308	12			D11308		11		YD160-YR328
6006	22	PA			1-11	28-41-11	D11308	1			GD01000	ST..	E		ALL
6007	20	PA			0-7	28-41-11	D04850J	16			D04850J	S/R			ALL
6008	20	PA			0-7	28-41-11	D04850J	15			D04850J		50		ALL
6009	20	PA			0-7	28-41-11	D04850J	51			D04850J	S/R			ALL
FRAA					0-0	28-41-11	D11308	9			D11308			FA	ALL
FRAB					0-0	28-41-11	D11308	19			D11308			FA	ALL
FRAC					0-0	28-41-11	D04850J	31	18		D04850J			FC	ALL

WIRE LIST

D280A108

91-21-11

Section W5580

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description	From			To			Effectivity				
	GA	CO	TY		Fam	FT-IN	Diagram	Equip	Term	Type		Splice	Equip	Term	Type
W5580															
286A5580															
RADAR BAY TO WHEEL WELL DISC STA 675L-CENTER TANK (continued)															
FRAD					0-0	28-41-11	D04850J	33	18		D04850J			FC	ALL

For training purposes only!

WIRE LIST

D280A108

91-21-11

Section W5580

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I W5592	286A5592			SEC 47 OVHT DETECTION TO SEC 48 OVHT DETECTION											
I 6001R	18	QZ			11-2	26-12-11	D00862		= 1		D00864		= 1		ALL

For training purposes only!

WIRE LIST
D280A108

91-21-11
Section W5590
Page 1 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Diagram	From				To				Effectivity		
	Wire No.	GA	CO TY			Fam	FT-IN	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W5603	286A5603			E3-2 SHELF (DFDAU) TO LH BRAKE PRESSURE XMTRS												
2001B	20	X2	AC		56-0	31-31-14	D43203P	B02				D00821	B			YC051-YC055
2001B	20	X2	AC		55-9	31-31-14	D43203P	B02				D00821	B			YC056-YD152
2001B	20	X2	AC		56-1	31-31-14	D43203P	B02				D00821	B			YD153-YL955
2001B	20	X2	AC		55-11	31-31-14	D43203P	B02				D00821	B			YL956-YL999, YR301-YR328
2001B	20	X2	AC		45-10	31-31-14	D43203P	B02				D00821	B			YN231-YN235
2001B	20	X2	AC		45-8	31-31-14	D43203P	B02				D00821	B			YN236-YN501
2001R	20	X2	AC		0-0	31-31-14	D43203P	B01				D00821	A			ALL
2001Z			AC		0-0	31-31-14	D43203P	PERG	1F			D00821	DED			ALL
2002B	20	X2	AD		56-0	31-31-14	D43203P	B04				D00821	D			YC051-YC055
2002B	20	X2	AD		55-9	31-31-14	D43203P	B04				D00821	D			YC056-YD152
2002B	20	X2	AD		56-1	31-31-14	D43203P	B04				D00821	D			YD153-YL955
2002B	20	X2	AD		55-11	31-31-14	D43203P	B04				D00821	D			YL956-YL999, YR301-YR328
2002B	20	X2	AD		45-10	31-31-14	D43203P	B04				D00821	D			YN231-YN235
2002B	20	X2	AD		45-8	31-31-14	D43203P	B04				D00821	D			YN236-YN501
2002R	20	X2	AD		0-0	31-31-14	D43203P	B03				D00821	C			ALL
2002Z			AD		0-0	31-31-14	D43203P	PERG	1F			D00821	DED			ALL
2003B	20	X2	AE		56-0	31-31-14	D43203P	B06				D00821	F			YC051-YC055
2003B	20	X2	AE		55-9	31-31-14	D43203P	B06				D00821	F			YC056-YD152
2003B	20	X2	AE		56-1	31-31-14	D43203P	B06				D00821	F			YD153-YL955
2003B	20	X2	AE		55-11	31-31-14	D43203P	B06				D00821	F			YL956-YL999, YR301-YR328
2003B	20	X2	AE		45-10	31-31-14	D43203P	B06				D00821	F			YN231-YN235
2003B	20	X2	AE		45-8	31-31-14	D43203P	B06				D00821	F			YN236-YN501
2003R	20	X2	AE		0-0	31-31-14	D43203P	B05				D00821	E			ALL
2003Z			AE		0-0	31-31-14	D43203P	PERG	1F			D00821	DED			ALL
2004B	20	X2	AF		56-0	31-31-14	D43203P	B08				D00821	H			YC051-YC055
2004B	20	X2	AF		55-9	31-31-14	D43203P	B08				D00821	H			YC056-YD152
2004B	20	X2	AF		56-1	31-31-14	D43203P	B08				D00821	H			YD153-YL955
2004B	20	X2	AF		55-11	31-31-14	D43203P	B08				D00821	H			YL956-YL999, YR301-YR328
2004B	20	X2	AF		45-10	31-31-14	D43203P	B08				D00821	H			YN231-YN235
2004B	20	X2	AF		45-8	31-31-14	D43203P	B08				D00821	H			YN236-YN501
2004R	20	X2	AF		0-0	31-31-14	D43203P	B07				D00821	G			ALL
2004Z			AF		0-0	31-31-14	D43203P	PERG	1F			D00821	DED			ALL
3001B	20	X3	AA		54-9	31-31-14	D43203P	A02				D02913	3			YC051-YC055
3001B	20	X3	AA		54-10	31-31-14	D43203P	A02				D02913	3			YC056-YD152

WIRE LIST

D280A108

91-21-11

Section W5600

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5603	286A5603				E3-2 SHELF (DFDAU) TO LH BRAKE PRESSURE XMTRS (continued)										
3001B	20	X3	AA		55-0	31-31-14	D43203P	A02			D02913	3			YD153-YL999, YR301-YR328
3001B	20	X3	AA		44-6	31-31-14	D43203P	A02			D02913	3			YN231-YN501
3001R	20	X3	AA		0-0	31-31-14	D43203P	A01			D02913	2			ALL
3001Y	20	X3	AA		0-0	31-31-14	D43203P	A03			D02913	1			ALL
3001Z			AA		0-0	31-31-14	D43203P	PERG	1F		D02913	DED			ALL
3002B	20	X3	AB		60-5	31-31-14	D43203P	A05			D02909	2			YC051-YC055
3002B	20	X3	AB		60-6	31-31-14	D43203P	A05			D02909	2			YC056-YD152
3002B	20	X3	AB		56-8	31-31-14	D43203P	A05			D02909	2			YD153-YL955
3002B	20	X3	AB		56-9	31-31-14	D43203P	A05			D02909	2			YL956-YL999, YR301-YR328
3002B	20	X3	AB		46-2	31-31-14	D43203P	A05			D02909	2			YN231-YN235
3002B	20	X3	AB		46-3	31-31-14	D43203P	A05			D02909	2			YN236-YN501
3002R	20	X3	AB		0-0	31-31-14	D43203P	A04			D02909	1			ALL
3002Y	20	X3	AB		0-0	31-31-14	D43203P	A06			D02909	3			ALL
3002Z			AB		0-0	31-31-14	D43203P	PERG	1F		D02909	DED			ALL
3003B	20	X3	BA		61-4	31-31-14	D43203P	A08			D11995	3			YD154-YD158
3003R	20	X3	BA		0-0	31-31-14	D43203P	A07			D11995	2			YD154-YD158
3003Y	20	X3	BA		0-0	31-31-14	D43203P	A09			D11995	1			YD154-YD158
3003Z			BA		0-0	31-31-14	D43203P	PERG	1F		D11995	DED			YD154-YD158
W5605	286A5605				E1-3 SHELF (DFDAU) TO RH BRAKE PRESSURE XMTRS										
3001B	20	X3	AA		55-4	31-31-14	D43205P	A02			D02915	3			YC051-YC055
3001B	20	X3	AA		55-7	31-31-14	D43205P	A02			D02915	3			YC056-YD152
3001B	20	X3	AA		54-11	31-31-14	D43205P	A02			D02915	3			YD153-YL999, YR301-YR328
3001B	20	X3	AA		44-5	31-31-14	D43205P	A02			D02915	3			YN231-YN501
3001R	20	X3	AA		0-0	31-31-14	D43205P	A01			D02915	2			ALL
3001Y	20	X3	AA		0-0	31-31-14	D43205P	A03			D02915	1			ALL
3001Z			AA		0-0	31-31-14	D43205P	PERG	1F		D02915	DED			ALL
3002B	20	X3	AB		57-10	31-31-14	D43205P	A05			D02911	2			YC051-YC055
3002B	20	X3	AB		58-1	31-31-14	D43205P	A05			D02911	2			YC056-YD152
3002B	20	X3	AB		58-4	31-31-14	D43205P	A05			D02911	2			YD153-YL999, YR301-YR328
3002B	20	X3	AB		47-10	31-31-14	D43205P	A05			D02911	2			YN231-YN501
3002R	20	X3	AB		0-0	31-31-14	D43205P	A04			D02911	1			ALL
3002Y	20	X3	AB		0-0	31-31-14	D43205P	A06			D02911	3			ALL
3002Z			AB		0-0	31-31-14	D43205P	PERG	1F		D02911	DED			ALL

WIRE LIST

D280A108

91-21-11

Section W5600

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5610		286A5610			E1 TO E2, E3										
0001	24		PK		10-3	31-31-15	D40348P	A01			D40940P	A01			YC051-YC055
0001	24		PK		10-5	31-31-15	D40348P	A01			D40940P	A01			YC056-YR328
0002	24		PK		10-3	31-31-15	D40348P	B01			D40940P	B01			YC051-YC055
0002	24		PK		10-5	31-31-15	D40348P	B01			D40940P	B01			YC056-YR328
0501	22		PA		23-9	SPARE	D40346J	11			D40348P	A02			YC051-YC055
0501	22		PA		23-6	SPARE	D40346J	11			D40348P	A02			YC056-YR328
0502	22		PA		23-9	SPARE	D40346J	12			D40348P	B02			YC051-YC055
0502	22		PA		23-6	SPARE	D40346J	12			D40348P	B02			YC056-YR328
0503	22		PA		23-9	SPARE	D40346J	13			D40348P	A03			YC051-YC055
0503	22		PA		23-6	SPARE	D40346J	13			D40348P	A03			YC056-YR328
0504	22		PA		23-9	49-62-11	D40346J	14			D40348P	B03			YC051-YC055
0504	22		PA		23-6	49-62-11	D40346J	14			D40348P	B03			YC056-YR328
0510	24		PK		10-0	32-42-11	D40344P	23			D40346J	54			ALL
0512	24		PK		10-0	32-42-11	D40344P	24			D40346J	34			ALL
0523	24		PK		28-5	29-33-11	D40346J	26			D40350P	B06			ALL
0524	24		PK		28-5	29-33-11	D40346J	27			D40350P	A07			ALL
0528	22		PA		21-11	32-41-11	D40344P	9			D40350P	B07			YC051-YC055
0528	22		PA		21-10	32-41-11	D40344P	9			D40350P	B07			YC056-YR328
0591	22		PA		10-0	32-41-11	D40344P	26			D40346J	25			ALL
0592	22		PA		22-0	27-83-11	D40940P	A02			D40344P	2			YC051-YC055
0592	22		PA		21-10	27-83-11	D40940P	A02			D40344P	2			YC056-YR328
2251B	22		X2	MA	22-0	32-41-11	D40940P	A09			D40344P	7			YC051-YC055
2251B	22		X2	MA	21-10	32-41-11	D40940P	A09			D40344P	7			YC056-YR328
2251R	22		X2	MA	0-0	32-41-11	D40940P	B08			D40344P	6			ALL
2251Z				MA	0-0	32-41-11	D40940P	B09			D40344P	8			ALL
2601B	24		Y2	SA	23-9	73-24-11	D40348P	A08			D40346J	20			YC051-YC055
2601B	24		Y2	SA	23-6	73-24-11	D40348P	A08			D40346J	20			YC056-YR328
2601R	24		Y2	SA	0-0	73-24-11	D40348P	B08			D40346J	19			ALL
2601Z				SA	0-0	73-24-11	D40348P	PERG	1F		D40346J	S/R			ALL
2602B	24		PL	SB	23-9	76-21-11	D40348P	A14			D40346J	3			YC051-YC055
2602B	24		PL	SB	23-6	76-21-11	D40348P	A14			D40346J	3			YC056-YR328
2602R	24		PL	SB	0-0	76-21-11	D40348P	B14			D40346J	4			ALL
2801B	24		Y2	A8	10-3	SPARE	D40348P	A05			D40940P	A04			YC051-YC055
2801B	24		Y2	A8	10-5	SPARE	D40348P	A05			D40940P	A04			YC056-YL959, YN231-YN235
2801R	24		Y2	A8	0-0	SPARE	D40348P	B05			D40940P	B04			YC051-YL959, YN231-YN235
2801Z				A8	0-0	SPARE	D40348P	PERG	1F		D40940P	PERG	1F		YC051-YL959, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W5610

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W5610	286A5610	E1 TO E2, E3 (continued)													
2802B	24	Y2	B8	10-3	SPARE	D40940P	A05		D40348P	A06			YC051-YC055		
2802B	24	Y2	B8	10-5	SPARE	D40940P	A05		D40348P	A06			YC056-YL959, YN231-YN235		
2802R	24	Y2	B8	0-0	SPARE	D40940P	B05		D40348P	B06			YC051-YL959, YN231-YN235		
2802Z			B8	0-0	SPARE	D40940P	PERG	1F	D40348P	PERG	1F		YC051-YL959, YN231-YN235		
6001	22	PA		28-5	78-32-51	D40346J	44		D40350P	A01			YC051-YC055		
6001	22	PA		28-3	78-32-51	D40346J	44		D40350P	A01			YC056-YR328		
6002	22	PA		28-5	78-32-51	D40346J	45		D40350P	B01			YC051-YC055		
6002	22	PA		28-3	78-32-51	D40346J	45		D40350P	B01			YC056-YR328		
6018R	22	PH		23-9	26-11-21	D40346J	42		D40348P	A12			YC051-YC055		
6018R	22	PH		23-6	26-11-21	D40346J	42		D40348P	A12			YC056-YR328		
6019R	22	PH		23-9	26-11-21	D40346J	23		D40348P	B12			YC051-YC055		
6019R	22	PH		23-6	26-11-21	D40346J	23		D40348P	B12			YC056-YR328		
6024R	20	PH		28-5	26-12-11	D40350P	A06		D40346J	15			YC051-YC055		
6024R	20	PH		28-3	26-12-11	D40350P	A06		D40346J	15			YC056-YR328		
6027	20	PA		23-9	76-21-11	D40348P	A15		D40346J	30			YC051-YC055		
6027	20	PA		23-6	76-21-11	D40348P	A15		D40346J	30			YC056-YR328		
6028R	22	PH		17-3	26-11-21	D40344P	31		D40348P	B15			YC051-YC055		
6028R	22	PH		17-0	26-11-21	D40344P	31		D40348P	B15			YC056-YR328		
6029R	22	PH		17-3	26-11-21	D40344P	30		D40348P	A16			YC051-YC055		
6029R	22	PH		17-0	26-11-21	D40344P	30		D40348P	A16			YC056-YR328		
6030R	22	PH		17-3	26-11-21	D40344P	29		D40348P	B16			YC051-YC055		
6030R	22	PH		17-0	26-11-21	D40344P	29		D40348P	B16			YC056-YR328		
6031R	22	PH		17-3	26-11-21	D40344P	28		D40348P	A17			YC051-YC055		
6031R	22	PH		17-0	26-11-21	D40344P	28		D40348P	A17			YC056-YR328		
6032R	22	PH		17-3	26-11-21	D40344P	17		D40348P	B17			YC051-YC055		
6032R	22	PH		17-0	26-11-21	D40344P	17		D40348P	B17			YC056-YR328		
6033R	22	PH		17-3	26-11-21	D40344P	18		D40348P	A18			YC051-YC055		
6033R	22	PH		17-0	26-11-21	D40344P	18		D40348P	A18			YC056-YR328		
6034R	20	PH		23-9	26-12-11	D40346J	48		D40348P	B18			YC051-YC055		
6034R	20	PH		23-6	26-12-11	D40346J	48		D40348P	B18			YC056-YR328		
6035R	20	PH		23-9	26-12-11	D40346J	43		D40348P	A19			YC051-YC055		
6035R	20	PH		23-6	26-12-11	D40346J	43		D40348P	A19			YC056-YR328		
6036R	22	PH		23-9	26-11-21	D40346J	24		D40348P	B19			YC051-YC055		
6036R	22	PH		23-6	26-11-21	D40346J	24		D40348P	B19			YC056-YR328		
6037R	22	PH		23-9	26-11-21	D40346J	47		D40348P	A20			YC051-YC055		
6037R	22	PH		23-6	26-11-21	D40346J	47		D40348P	A20			YC056-YR328		

WIRE LIST

D280A108

91-21-11

Section W5610

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5610		286A5610			E1 TO E2, E3 (continued)										
	6038R	20		PH	10-0	26-12-11	D40346J		29		D40344P	21			ALL
	6039R	20		PH	10-0	26-12-11	D40344P		20		D40346J	28			ALL
	6040R	20		PH	10-0	26-12-11	D40346J		40		D40344P	19			ALL
	6041	20		PA	23-9	80-11-11	D40346J		9		D40348P	B07			YC051-YC055
	6041	20		GK	23-6	80-11-11	D40346J		9		D40348P	B07			YC056-YR328
	6042R	22		PH	23-9	26-12-11	D40346J		31		D40348P	A09			YC051-YC055
	6042R	22		PH	23-6	26-12-11	D40346J		31		D40348P	A09			YC056-YR328
	6043	24		PK	23-9	80-11-11	D40346J		8		D40348P	A07			YC051-YC055
	6043	24		PK	23-6	80-11-11	D40346J		8		D40348P	A07			YC056-YR328
	6048	24		PK	10-3	31-31-15	D40940P		A07		D40348P	A10			YC053-YC055
	6048	24		PK	10-5	31-31-15	D40940P		A07		D40348P	A10			YC056-YD158
	6048	24		PK	10-5	26-16-21	D40940P		A07		D40348P	A10			YD160-YR328
	6049	24		PK	10-3	31-31-15	D40940P		B07		D40348P	B10			YC053-YC055
	6049	24		PK	10-5	31-31-15	D40940P		B07		D40348P	B10			YC056-YD158
	6049	24		PK	10-5	26-16-22	D40940P		B07		D40348P	B10			YD160-YR328
W5612		286A5612			AP0600B TO E/E BAY										
	0001	20		PA	5-2	SPARE	D40358P		A01		D40362P	A01			YC051-YC055
	0001	20		PA	5-3	SPARE	D40358P		A01		D40362P	A01			YC056-YR328
	0204	20		PA	23-3	27-23-11	D40352P		31		D40362P	A09			YD154-YR328
	0205	20		GA	46-0	27-25-11	D11939		A1		D46043P	12			YC051-YD153
	0205	20		PA	23-3	27-25-11	D40352P		20		D40362P	A08			YD154-YR328
	0206	20		GA	46-0	27-25-11	D11941		A1		D43263P	A11			YC051-YD153
	0206	20		PA	23-3	27-25-11	D40352P		22		D40362P	B03			YD154-YR328
	0207	24		PK	18-2	24-28-41	D40352P		7		D40930P	A07			YD154-YR328
	0208	24		PK	18-2	24-28-41	D40352P		25		D40930P	B07			YD154-YR328
	0501	20		CQ	25-1	49-41-11	D40352P		24		D40360P	25			YC051-YC055
	0501	20		CQ	25-2	49-41-11	D40352P		24		D40360P	25			YC056-YR328
	0505	20		CQ	25-1	49-62-11	D40352P		3		D40360P	18			YC051-YC055
	0505	20		CQ	25-2	49-62-11	D40352P		3		D40360P	18			YC056-YR328
	0507	24		B6	25-1	24-31-11	D40360P		17		D40352P	13			YC051-YC055
	0507	24		B6	25-2	24-31-11	D40360P		17		D40352P	13			YC056-YR328
	0508	20		CQ	23-6	24-11-11	D40352P		4		D40358P	F			ALL
	0509	20		CQ	18-7	24-11-21	D40352P		6		D40356P	F			YC051-YC055
	0509	20		CQ	18-5	24-11-21	D40352P		6		D40356P	F			YC056-YR328
	0510	22		PA	10-9	24-23-11	D40358P		A05		D40356P	A04			ALL
	0511	22		PA	10-9	24-23-11	D40358P		A06		D40356P	B04			ALL
	0512	20		CQ	18-7	24-41-11	D40352P		23		D40356P	G			YC051-YC055
	0512	20		CQ	18-5	24-41-11	D40352P		23		D40356P	G			YC056-YR328

WIRE LIST

D280A108

91-21-11

Section W5610

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description		From				To					
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5612	286A5612			AP0600B TO E/E BAY (continued)											
0515	24		PK		10-9	24-28-41	D40356P	A05			D40358P	A07			ALL
0516	24		PK		10-9	24-28-41	D40356P	B05			D40358P	A08			ALL
0518	08		CQ		15-0	24-32-11	TB5060G	8	E		TB5420	1	P		YC051-YC055
0518	08		CQ		15-3	24-32-11	TB5060G	8	E		TB5420	1	P		YC056-YR328
0521	20		CQ		23-6	24-22-31	D40352P	8			D40358P	G			ALL
0522	22		PA		10-6	24-22-31	D40930P	A01			D40358P	B06			ALL
0524	22		PA		10-6	24-22-31	D40930P	B01			D40358P	B07			ALL
0525	22		PA		10-6	24-22-31	D40930P	A02			D40358P	B01			ALL
0526	22		PA		10-6	24-22-31	D40930P	B04			D40358P	A02			ALL
0531	22		PA		12-4	29-11-11	D40360P	7			D40356P	A01			ALL
0536	22		PA		18-4	24-41-11	D40352P	5			D40930P	A05			YC051-YC055
0536	22		PA		18-2	24-41-11	D40352P	5			D40930P	A05			YC056-YR328
0539	22		CQ		10-6	24-22-11	D40930P	B05			D40358P	A09			ALL
0540	22		CQ		10-6	24-22-31	D40930P	A06			D40358P	B09			ALL
0541	22		CQ		23-3	24-28-11	D40352P	14			D40362P	B02			ALL
0542	22		CQ		23-3	24-28-11	D40352P	16			D40362P	A02			ALL
0543	24		B6		23-3	24-33-13	D40352P	18			D40362P	A06			ALL
0544	24		B6		23-3	24-33-13	D40352P	29			D40362P	B06			ALL
0545	24		B6		23-3	24-33-13	D40352P	15			D40362P	A04			ALL
0546	24		B6		23-3	24-33-13	D40352P	19			D40362P	B04			ALL
0547	24		B6		23-3	24-33-13	D40352P	30			D40362P	A05			ALL
0548	24		B6		23-3	24-33-13	D40352P	26			D40362P	B05			ALL
0549	20		CQ		18-4	27-81-51	D40352P	32			D40930P	A03			YC051-YC055
0549	20		CQ		18-2	27-81-51	D40352P	32			D40930P	A03			YC056-YR328
0550	22		PA		23-3	31-33-01	D40352P	12			D40362P	B10			ALL
0553	22		PA		10-6	24-22-31	D40930P	B06			D40358P	A03			ALL
0554	24		PK		23-3	26-14-11	D40362P	A03			D40352P	21			YC051-YD153
0554	24		PK		23-3	26-14-11	D40352P	21			D40362P	A03			YD154-YD170
0554	24		PK		23-3	SPARE	D40352P	21			D40362P	A03			YL951-YR328
0555	22		PA		23-3	SPARE	D40352P	17			D40362P	A10			YD154-YD170, YN231-YN235
0555	22		PA		23-3	31-35-03	D40352P	17			D40362P	A10			YL951-YL999, YN236-YR328
1100	24		Y1	BN	7-4	31-31-15	D40360P	2			D40362P	B01			YC051-YC055
1100	24		Y1	BN	7-5	31-31-15	D40360P	2			D40362P	B01			YC056-YR328
1100Z				BN	0-0	31-31-15	D40360P	DED			D40362P	DED			ALL
1201	20		X1	DA	12-4	33-44-12	D40356P	B01			D40360P	1			ALL
1201Z				DA	0-0	33-44-12	D40356P	DED			D40360P	DED			ALL
2201B	22		PB	KA	3-3	24-22-11	D40360P	11			D40358P	B03			ALL

WIRE LIST

D280A108

91-21-11

Section W5610

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5612		286A5612			AP0600B TO E/E BAY (continued)											
2201R		22		PB	KA	0-0	24-22-11	D40360P		10		D40358P		B02		ALL
2203B		22		PB	KC	12-1	24-23-11	D40360P		9		D40930P		B03		ALL
2203R		22		PB	KC	0-0	24-23-11	D40360P		8		D40930P		A04		ALL
2204B		24		Y2	KD	23-6	SPARE	D40352P		28		D40358P		B05		YD154-YR328
2204R		24		Y2	KD	0-0	SPARE	D40352P		9		D40358P		B04		YD154-YR328
2204Z					KD	0-0	SPARE	D40352P		DED		D40358P		DED		YD154-YR328
2206B		22		PB	KF	3-3	24-22-31	D40360P		13		D40358P		B10		ALL
2206R		22		PB	KF	0-0	24-22-31	D40360P		12		D40358P		A10		ALL
2207B		22		PB	KG	5-3	SPARE	D40358P		B08		D40362P		B07		YD154-YR328
2207R		22		PB	KG	0-0	SPARE	D40358P		A04		D40362P		A07		YD154-YR328
6001		22		PA		12-4	30-11-11	D40360P		4		D40356P		A02		ALL
6002		22		PA		12-4	30-11-11	D40360P		5		D40356P		B02		ALL
6012R		20		PH		25-1	26-11-31	D40352P		1		D40360P		15		YC051-YC055
6012R		20		PH		25-2	26-11-31	D40352P		1		D40360P		15		YC056-YR328
W5615		286A5615			SATCOM E6-1 TO E4-1,E5-2											
0006		24		PK		115-1	31-31-17	D06103P		6		D45001J		A03		YC051-YC055
0006		24		PK		115-3	31-31-17	D06103P		6		D45001J		A03		YC056-YD157
0007		24		PK		115-1	31-31-17	D06103P		7		D45001J		B03		YC051-YC055
0007		24		PK		115-3	31-31-17	D06103P		7		D45001J		B03		YC056-YD157
0008		22		PA		114-11	23-15-15	D06105P		4		D45001J		A05		YC051-YC055
0008		22		PA		115-1	23-15-15	D06105P		4		D45001J		A05		YC056-YD157
0009		24		PK		103-3	23-15-12	D06103P		8		D41101P		B05		YC051-YD157
0010		24		PK		103-3	23-15-12	D06103P		9		D41101P		B06		YC051-YD157
0011		24		PK		103-1	23-15-15	D06105P		17		D41101P		B01		YC051-YC055
0011		24		PK		103-2	23-15-15	D06105P		17		D41101P		B01		YC056-YD157
0012		24		PK		103-1	23-15-15	D06105P		18		D41101P		B02		YC051-YC055
0012		24		PK		103-2	23-15-15	D06105P		18		D41101P		B02		YC056-YD157
0013		24		PK		103-1	23-15-15	D06105P		19		D41101P		B03		YC051-YC055
0013		24		PK		103-2	23-15-15	D06105P		19		D41101P		B03		YC056-YD157
0014		24		PK		103-1	23-15-15	D06105P		20		D41101P		B04		YC051-YC055
0014		24		PK		103-2	23-15-15	D06105P		20		D41101P		B04		YC056-YD157
0015		22		PA		103-1	23-15-15	D06105P		1		D41101P		A10		YC051-YC055
0015		22		PA		103-2	23-15-15	D06105P		1		D41101P		A10		YC056-YD157
2501B		22		X2	AA	115-1	23-27-15	D06103P		3		D45001J		B01		YC051-YC055
2501B		22		X2	AA	115-3	23-27-15	D06103P		3		D45001J		B01		YC056-YD157
2501R		22		X2	AA	0-0	23-27-15	D06103P		2		D45001J		A01		YC051-YD157
2501Z					AA	0-0	23-27-15	D06103P		S/R		D45001J		PERG	1F	YC051-YD157
2502B		24		Y2	AB	115-1	23-15-12	D06103P		5		D45001J		B02		YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5610

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From				To						
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5615	286A5615			SATCOM E6-1 TO E4-1,E5-2 (continued)											
2502B	24	Y2	AB		115-3	23-15-12	D06103P		5		D45001J	B02			YC056-YD157
2502R	24	Y2	AB		0-0	23-15-12	D06103P		4		D45001J	A02			YC051-YD157
2502Z			AB		0-0	23-15-12	D06103P		S/R		D45001J	PERG	1F		YC051-YD157
2503B	24	Y2	AC		114-11	34-21-13	D06105P		3		D45001J	B04			YC051-YC055
2503B	24	Y2	AC		115-1	34-21-13	D06105P		3		D45001J	B04			YC056-YD157
2503R	24	Y2	AC		0-0	34-21-13	D06105P		2		D45001J	A04			YC051-YD157
2503Z			AC		0-0	34-21-13	D06105P		S/R		D45001J	PERG	1F		YC051-YD157
2504B	22	X2	AD		114-11	34-61-18	D06105P		8		D45001J	B07			YC051-YC055
2504B	22	X2	AD		115-1	SPARE	D06105P		8		D45001J	B07			YC056-YC057
2504B	22	X2	AD		115-1	34-61-18	D06105P		8		D45001J	B07			YC058
2504B	22	X2	AD		115-1	31-32-15	D06105P		8		D45001J	B07			YC059-YD157
2504R	22	X2	AD		0-0	34-61-18	D06105P		7		D45001J	A07			YC051-YC055, YC058
2504R	22	X2	AD		0-0	SPARE	D06105P		7		D45001J	A07			YC056-YC057
2504R	22	X2	AD		0-0	31-32-15	D06105P		7		D45001J	A07			YC059-YD157
2504Z			AD		0-0	34-61-18	D06105P		S/R		D45001J	PERG	1F		YC051-YC055, YC058
2504Z			AD		0-0	SPARE	D06105P		S/R		D45001J	PERG	1F		YC056-YC057
2504Z			AD		0-0	31-32-15	D06105P		S/R		D45001J	PERG	1F		YC059-YD157
2505B	22	X2	AE		114-11	23-15-15	D06105P		6		D45001J	B06			YC051-YC055
2505B	22	X2	AE		115-1	23-15-15	D06105P		6		D45001J	B06			YC056-YD157
2505R	22	X2	AE		0-0	23-15-15	D06105P		5		D45001J	A06			YC051-YD157
2505Z			AE		0-0	23-15-15	D06105P		S/R		D45001J	PERG	1F		YC051-YD157
2506B	24	Y2	AF		114-11	34-61-23	D06105P		10		D45001J	B08			YC051-YC055
2506B	24	Y2	AF		115-1	34-61-23	D06105P		10		D45001J	B08			YC056-YD157
2506R	24	Y2	AF		0-0	34-61-23	D06105P		9		D45001J	A08			YC051-YD157
2506Z			AF		0-0	34-61-23	D06105P		S/R		D45001J	PERG	1F		YC051-YD157
2507B	24	Y2	AG		114-11	23-15-15	D06105P		12		D45001J	B09			YC051-YC055
2507B	24	Y2	AG		115-1	23-15-15	D06105P		12		D45001J	B09			YC056-YD157
2507R	24	Y2	AG		0-0	23-15-15	D06105P		11		D45001J	A09			YC051-YD157
2507Z			AG		0-0	23-15-15	D06105P		S/R		D45001J	PERG	1F		YC051-YD157
2508B	24	Y2	AH		114-11	34-61-23	D06105P		14		D45001J	B11			YC051-YC055
2508B	24	Y2	AH		115-1	34-61-23	D06105P		14		D45001J	B11			YC056-YD157
2508R	24	Y2	AH		0-0	34-61-23	D06105P		13		D45001J	A11			YC051-YD157
2508Z			AH		0-0	34-61-23	D06105P		S/R		D45001J	PERG	1F		YC051-YD157
2509B	24	Y2	AI		114-11	SPARE	D06105P		16		D45001J	B12			YC051-YC055
2509B	24	Y2	AI		115-1	SPARE	D06105P		16		D45001J	B12			YC056-YD157
2509R	24	Y2	AI		0-0	SPARE	D06105P		15		D45001J	A12			YC051-YD157
2509Z			AI		0-0	SPARE	D06105P		S/R		D45001J	PERG	1F		YC051-YD157
2510B	24	Y2	AJ		103-3	23-15-12	D06103P		11		D41101P	A08			YC051-YD157
2510R	24	Y2	AJ		0-0	23-15-12	D06103P		10		D41101P	A07			YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W5610

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5615	286A5615			SATCOM E6-1 TO E4-1,E5-2 (continued)											
2510Z				AJ	0-0	23-15-12	D06103P	20			D41101P	A09			YC051-YD157
2511B	24	Y2		AK	103-3	23-15-12	D06103P	13			D41101P	B08			YC051-YD157
2511R	24	Y2		AK	0-0	23-15-12	D06103P	12			D41101P	B07			YC051-YD157
2511Z				AK	0-0	23-15-12	D06103P	21			D41101P	B10			YC051-YD157
2512B	24	Y2		AL	103-3	23-15-13	D06103P	15			D41101P	A02			YC051-YD157
2512R	24	Y2		AL	0-0	23-15-13	D06103P	14			D41101P	A01			YC051-YD157
2512Z				AL	0-0	23-15-13	D06103P	16			D41101P	A03			YC051-YD157
2513B	24	Y2		AM	103-3	23-15-13	D06103P	18			D41101P	A05			YC051-YD157
2513R	24	Y2		AM	0-0	23-15-13	D06103P	17			D41101P	A04			YC051-YD157
2513Z				AM	0-0	23-15-13	D06103P	19			D41101P	A06			YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W5610

Page 7 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description		From				To					
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5719	286A5719			INTERRACK E1-1 TO E1-2,E1-3 AND E4-2											
0001	24		PK		10-10	34-53-11	D41211J		1		D41509P		1		YC051-YL952, YN231-YN233
0001	24		PK		11-1	34-53-11	D41211J		1		D41509P		1		YL953-YL999, YN234-YR328
0002	24		PK		10-10	34-53-11	D41211J		2		D41509P		2		YC051-YL952, YN231-YN233
0002	24		PK		11-1	34-53-11	D41211J		2		D41509P		2		YL953-YL999, YN234-YR328
0003	24		PK		10-10	34-53-11	D41211J		3		D41509P		3		YC051-YL952, YN231-YN233
0003	24		PK		11-1	34-53-11	D41211J		3		D41509P		3		YL953-YL999, YN234-YR328
0004	24		PK		10-10	34-53-11	D41211J		4		D41509P		4		YC051-YL952, YN231-YN233
0004	24		PK		11-1	34-53-11	D41211J		4		D41509P		4		YL953-YL999, YN234-YR328
0005	24		PK		10-10	34-53-11	D41211J		5		D41509P		5		YC051-YL952, YN231-YN233
0005	24		PK		11-1	34-53-11	D41211J		5		D41509P		5		YL953-YL999, YN234-YR328
0006	24		PK		10-10	34-53-11	D41211J		6		D41509P		6		YC051-YL952, YN231-YN233
0006	24		PK		11-1	34-53-11	D41211J		6		D41509P		6		YL953-YL999, YN234-YR328
0007	24		PK		10-10	34-53-11	D41211J		7		D41509P		7		YC051-YL952, YN231-YN233
0007	24		PK		11-1	34-53-11	D41211J		7		D41509P		7		YL953-YL999, YN234-YR328
0008	24		PK		10-10	34-53-11	D41211J		8		D41509P		8		YC051-YL952, YN231-YN233
0008	24		PK		11-1	34-53-11	D41211J		8		D41509P		8		YL953-YL999, YN234-YR328
0009	24		PK		10-10	34-53-11	D41211J		9		D41509P		9		YC051-YL952, YN231-YN233
0009	24		PK		11-1	34-53-11	D41211J		9		D41509P		9		YL953-YL999, YN234-YR328
0010	24		PK		10-10	34-53-11	D41211J		10		D41509P		10		YC051-YL952, YN231-YN233

WIRE LIST

D280A108

91-21-11

Section W5710

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W5719	286A5719				INTERRACK E1-1 TO E1-2,E1-3 AND E4-2 (continued)											
0010	24		PK		11-1	34-53-11	D41211J		10			D41509P	10			YL953-YL999, YN234-YR328
0011	24		PK		10-10	34-53-11	D41211J		11			D41509P	11			YC051-YL952, YN231-YN233
0011	24		PK		11-1	34-53-11	D41211J		11			D41509P	11			YL953-YL999, YN234-YR328
0012	24		PK		10-10	34-53-11	D41211J		12			D41509P	12			YC051-YL952, YN231-YN233
0012	24		PK		11-1	34-53-11	D41211J		12			D41509P	12			YL953-YL999, YN234-YR328
0013	24		PK		10-10	34-53-11	D41211J		13			D41509P	13			YC051-YL952, YN231-YN233
0013	24		PK		11-1	34-53-11	D41211J		13			D41509P	13			YL953-YL999, YN234-YR328
0014	24		PK		10-10	34-53-11	D41211J		14			D41509P	14			YC051-YL952, YN231-YN233
0014	24		PK		11-1	34-53-11	D41211J		14			D41509P	14			YL953-YL999, YN234-YR328
0015	24		PK		10-10	34-53-11	D41211J		15			D41509P	15			YC051-YL952, YN231-YN233
0015	24		PK		11-1	34-53-11	D41211J		15			D41509P	15			YL953-YL999, YN234-YR328
0016	24		PK		10-10	34-53-11	D41211J		16			D41509P	16			YC051-YL952, YN231-YN233
0016	24		PK		11-1	34-53-11	D41211J		16			D41509P	16			YL953-YL999, YN234-YR328
0017	24		PK		10-10	34-53-11	D41211J		17			D41509P	17			YC051-YL952, YN231-YN233
0017	24		PK		11-1	34-53-11	D41211J		17			D41509P	17			YL953-YL999, YN234-YR328
0018	24		PK		10-10	34-53-11	D41211J		18			D41509P	18			YC051-YL952, YN231-YN233
0018	24		PK		11-1	34-53-11	D41211J		18			D41509P	18			YL953-YL999, YN234-YR328
0019	24		PK		10-10	34-53-11	D41211J		19			D41509P	19			YC051-YL952, YN231-YN233
0019	24		PK		11-1	34-53-11	D41211J		19			D41509P	19			YL953-YL999, YN234-YR328

WIRE LIST

D280A108

91-21-11

Section W5710

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W5719	286A5719				INTERRACK E1-1 TO E1-2,E1-3 AND E4-2 (continued)										
0020	24		PK		10-10	34-53-11	D41211J		20		D41509P		20		YC051-YL952, YN231-YN233
0020	24		PK		11-1	34-53-11	D41211J		20		D41509P		20		YL953-YL999, YN234-YR328
0021	24		PK		10-10	34-53-11	D41211J		21		D41509P		21		YC051-YL952, YN231-YN233
0021	24		PK		11-1	34-53-11	D41211J		21		D41509P		21		YL953-YL999, YN234-YR328
0022	24		PK		10-10	34-53-11	D41211J		22		D41509P		22		YC051-YL952, YN231-YN233
0022	24		PK		11-1	34-53-11	D41211J		22		D41509P		22		YL953-YL999, YN234-YR328
0023	24		PK		10-10	34-53-11	D41211J		23		D41509P		23		YC051-YL952, YN231-YN233
0023	24		PK		11-1	34-53-11	D41211J		23		D41509P		23		YL953-YL999, YN234-YR328
0024	24		PK		10-10	34-53-11	D41211J		24		D41509P		24		YC051-YL952, YN231-YN233
0024	24		PK		11-1	34-53-11	D41211J		24		D41509P		24		YL953-YL999, YN234-YR328
0025	24		PK		10-10	34-53-11	D41211J		25		D41509P		25		YC051-YL952, YN231-YN233
0025	24		PK		11-1	34-53-11	D41211J		25		D41509P		25		YL953-YL999, YN234-YR328
0026	24		PK		10-10	SPARE	D41211J		26		D41509P		26		YC051-YL952, YN231-YN233
0026	24		PK		11-1	SPARE	D41211J		26		D41509P		26		YL953-YL999, YN234-YR328
0027	24		PK		10-10	SPARE	D41211J		27		D41509P		27		YC051-YL952, YN231-YN233
0027	24		PK		11-1	SPARE	D41211J		27		D41509P		27		YL953-YL999, YN234-YR328
0028	20		PA		10-10	SPARE	D41211J		28		D41509P		28		YC051-YL952, YN231-YN233
0028	20		PA		11-1	SPARE	D41211J		28		D41509P		28		YL953-YL999, YN234-YR328
0029	20		CQ		24-5	22-11-11	D41125P		A07		D42111P		B01		YC051-YC055
0029	20		CQ		25-1	22-11-11	D41125P		A07		D42111P		B01		YC056-YL952, YN231-YN233

WIRE LIST

D280A108

91-21-11

Section W5710

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	
Wire No.	GA CO TY	Fam FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice Effectivity	
W5719	286A5719	INTERRACK E1-1 TO E1-2,E1-3 AND E4-2 (continued)			
0029	20 CQ	25-2 22-11-11	D41125P A07	D42111P B01	YL953-YL999, YN234-YR328
0030	22 PA	24-5 SPARE	D41125P B07	D42111P B02	YC051-YC055
0030	22 PA	25-1 SPARE	D41125P B07	D42111P B02	YC056-YL952, YN231-YN233
0030	22 PA	25-2 SPARE	D41125P B07	D42111P B02	YL953-YL999, YN234-YR328
0031	20 CQ	24-5 22-11-12	D41125P A11	D42111P A01	YC051-YC055
0031	20 CQ	25-1 22-11-12	D41125P A11	D42111P A01	YC056-YL952, YN231-YN233
0031	20 CQ	25-2 22-11-12	D41125P A11	D42111P A01	YL953-YL999, YN234-YR328
0032	20 CQ	24-5 22-11-12	D41125P B11	D42111P A02	YC051-YC055
0032	20 CQ	25-1 22-11-12	D41125P B11	D42111P A02	YC056-YL952, YN231-YN233
0032	20 CQ	25-2 22-11-12	D41125P B11	D42111P A02	YL953-YL999, YN234-YR328
0033	22 PA	4-8 SPARE	D41125P A12	D41509P 40	YC051-YD157
0034	22 PA	4-8 23-42-11	D41125P B12	D41509P 39	ALL
0035	20 PA	4-8 SPARE	D41125P A13	D41509P 35	YC051-YD157
0036	20 PA	4-8 SPARE	D41125P B13	D41509P 36	ALL
0037	22 PA	4-8 23-42-11	D41125P A10	D41509P 37	YC051-YD157
0037	22 PA	4-8 SPARE	D41125P A10	D41509P 37	YD158-YR328
0038	24 PK	4-8 SPARE	D41125P B10	D41509P 38	ALL
0039	20 PA	11-4 SPARE	D41211J 39	D41125P A16	YC051-YL952, YN231-YN233
0039	20 PA	11-7 SPARE	D41211J 39	D41125P A16	YL953-YL999, YN234-YR328
0041	22 PA	11-4 SPARE	D41125P B16	D41211J 41	YC051-YL952, YN231-YN233
0041	22 PA	11-7 SPARE	D41125P B16	D41211J 41	YL953-YL999, YN234-YR328
0042	22 PA	4-8 31-31-17	D41125P B18	D41509P 42	ALL
0043	22 PA	11-4 SPARE	D41211J 40	D41125P A18	YC051-YL952, YN231-YN233
0043	22 PA	11-7 SPARE	D41211J 40	D41125P A18	YL953-YL999, YN234-YR328
0045	22 CQ	24-5 27-54-11	D41125P B19	D42111P B03	YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5710

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5719	286A5719				INTERRACK E1-1 TO E1-2,E1-3 AND E4-2 (continued)											
0045	22		CQ		25-1	27-54-11		D41125P	B19			D42111P	B03			YC056-YL952, YN231-YN233
0045	22		CQ		25-2	27-54-11		D41125P	B19			D42111P	B03			YL953-YL999, YN234-YR328
0049	22		PA		10-10	34-31-11		D41509P	41			D41211J	49			YC051-YL952, YN231-YN233
0049	22		PA		11-1	34-31-11		D41509P	41			D41211J	49			YL953-YL999, YN234-YR328
0051	22		PA		11-4	SPARE		D41211J	31			D41125P	B15			YC051-YL952, YN231-YN233
0051	22		PA		11-7	SPARE		D41211J	31			D41125P	B15			YL953-YL999, YN234-YR328
0052	20		CQ		24-5	27-81-51		D41125P	B17			D42111P	B04			YC051-YC055
0052	20		CQ		25-1	27-81-51		D41125P	B17			D42111P	B04			YC056-YL952, YN231-YN233
0052	20		CQ		25-2	27-81-51		D41125P	B17			D42111P	B04			YL953-YL999, YN234-YR328
0053	20		CQ		24-5	27-81-51		D41125P	B20			D42111P	B05			YC051-YC055
0053	20		CQ		25-1	27-81-51		D41125P	B20			D42111P	B05			YC056-YL952, YN231-YN233
0053	20		CQ		25-2	27-81-51		D41125P	B20			D42111P	B05			YL953-YL999, YN234-YR328
0063	24		PK		25-1	21-31-24		D41125P	A17			D42111P	A10			YD158-YL952, YN231-YN233
0063	24		PK		25-2	21-31-24		D41125P	A17			D42111P	A10			YL953-YL999, YN234-YR328
2001B	24		Y2	A	11-4	34-45-21		D41211J	30			D41125P	A06			YC051-YL952, YN231-YN233
2001B	24		Y2	A	11-7	34-45-21		D41211J	30			D41125P	A06			YL953-YL999, YN234-YR328
2001R	24		Y2	A	0-0	34-45-21		D41211J	29			D41125P	A05			ALL
2001Z				A	0-0	34-45-21		D41211J	S/R			D41125P	PERG	1F		ALL
2002B	24		Y2	B	11-4	34-45-21		D41211J	34			D41125P	B06			YC051-YL952, YN231-YN233
2002B	24		Y2	B	11-7	34-45-21		D41211J	34			D41125P	B06			YL953-YL999, YN234-YR328
2002R	24		Y2	B	0-0	34-45-21		D41211J	33			D41125P	B05			ALL
2002Z				B	0-0	34-45-21		D41211J	S/R			D41125P	PERG	1F		ALL

WIRE LIST

D280A108

91-21-11

Section W5710

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type		Splice
W5719	286A5719				INTERRACK E1-1 TO E1-2,E1-3 AND E4-2 (continued)											
2003B	24		Y2	C	11-4	34-55-11	D41211J	36			D41125P	A02			YC051-YL952, YN231-YN233	
2003B	24		Y2	C	11-7	34-55-11	D41211J	36			D41125P	A02			YL953-YL999, YN234-YR328	
2003R	24		Y2	C	0-0	34-55-11	D41211J	35			D41125P	A01	1F		ALL	
2003Z				C	0-0	34-55-11	D41211J	S/R			D41125P	PERG			ALL	
2004B	24		Y2	D	11-4	SPARE	D41211J	38			D41125P	B02			YC051-YC052	
2004B	24		Y2	D	11-4	34-58-11	D41211J	38			D41125P	B02			YC053-YL952, YN231-YN233	
2004B	24		Y2	D	11-7	34-58-11	D41211J	38			D41125P	B02			YL953-YL999, YN234-YR328	
2004R	24		Y2	D	0-0	SPARE	D41211J	37			D41125P	B01	1F		YC051-YC052	
2004R	24		Y2	D	0-0	34-58-11	D41211J	37			D41125P	B01			YC053-YR328	
2004Z				D	0-0	SPARE	D41211J	S/R			D41125P	PERG			YC051-YC052	
2004Z				D	0-0	34-58-11	D41211J	S/R			D41125P	PERG			YC053-YR328	
2005B	24		Y2	E	4-8	SPARE	D41125P	A04			D41509P	46	AA		ALL	
2005R	24		Y2	E	0-0	SPARE	D41125P	A03			D41509P	45			ALL	
2005Z				E	0-0	SPARE	D41125P	PERG	1F		D41509P				ALL	
2006B	24		Y2	F	4-8	SPARE	D41125P	B04			D41509P	50			ALL	
2006R	24		Y2	F	0-0	SPARE	D41125P	B03			D41509P	49	AC		ALL	
2006Z				F	0-0	SPARE	D41125P	PERG	1F		D41509P				ALL	
2007B	22		PB	AB	24-5	24-28-41	D41125P	A20			D42111P	A04			YC051-YC055	
2007B	22		PB	AB	25-1	24-28-41	D41125P	A20			D42111P	A04			YC056-YL952, YN231-YN233	
2007B	22		PB	AB	25-2	24-28-41	D41125P	A20			D42111P	A04			YL953-YL999, YN234-YR328	
2007R	22		PB	AB	0-0	24-28-41	D41125P	A19			D42111P	A03			ALL	
2008B	24		Y2	G	4-8	34-21-23	D41125P	B08			D41509P	33	AE		ALL	
2008R	24		Y2	G	0-0	34-21-23	D41125P	A08			D41509P	32			ALL	
2008Z				G	0-0	34-21-23	D41125P	PERG	1F		D41509P				ALL	
2009B	24		Y2	H	4-8	34-21-13	D41125P	B09			D41509P	30			ALL	
2009R	24		Y2	H	0-0	34-21-13	D41125P	A09			D41509P	29	AG		ALL	
2009Z				H	0-0	34-21-13	D41125P	PERG	1F		D41509P				ALL	
2010B	24		Y2	J	4-8	SPARE	D41125P	A15			D41509P	44			ALL	
2010R	24		Y2	J	0-0	SPARE	D41125P	A14			D41509P	43			ALL	
2010Z				J	0-0	SPARE	D41125P	PERG	1F		D41509P	S/R			ALL	
2011B	24		Y2	K	10-10	SPARE	D41211J	44			D41509P	53			YC051-YL952, YN231-YN233	

WIRE LIST

D280A108

91-21-11

Section W5710

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5719	286A5719				INTERRACK E1-1 TO E1-2,E1-3 AND E4-2 (continued)										
2011B	24	Y2	K		11-1	SPARE	D41211J	44			D41509P	53			YL953-YL999, YN234-YR328
2011R	24	Y2	K		0-0	SPARE	D41211J	43			D41509P	52			ALL
2011Z			K		0-0	SPARE	D41211J	S/R			D41509P	S/R			ALL
2017B	24	Y2	CR		11-4	22-11-51	D41211J	48			D41125P	A13			YD158-YL952, YN231-YN233
2017B	24	Y2	CR		11-7	22-11-51	D41211J	48			D41125P	A13			YL953-YL999, YN234-YR328
2017R	24	Y2	CR		0-0	22-11-51	D41211J	47			D41125P	A12			YD158-YR328
2017Z			CR		0-0	22-11-51	D41211J	S/R			D41125P	PERG	1F		YD158-YR328
FRAA					0-0	SPARE	D41509P			AA	D41509P	S/R			ALL
FRAB					0-0	SPARE	D41509P			AA	D41509P	47			ALL
FRAC					0-0	SPARE	D41509P	S/R			D41509P			AC	ALL
FRAD					0-0	SPARE	D41509P	51			D41509P			AC	ALL
FRAE					0-0	34-21-23	D41509P			AE	D41509P	S/R			ALL
FRAF					0-0	34-21-23	D41509P			AE	D41509P	34			ALL
FRAG					0-0	34-21-13	D41509P			AG	D41509P	S/R			ALL
FRAH					0-0	34-21-13	D41509P			AG	D41509P	31			ALL

WIRE LIST

D280A108

91-21-11

Section W5710

Page 7 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5721	286A5721			E1-1 TO E1-2 TO E1-4											
0002	22		PA		11-7	22-11-11	D41121P	A02			D41129J	2			ALL
0003	20		PA		11-7	22-11-11	D41121P	A03			D41129J	3			ALL
0004	20		PA		11-7	22-11-11	D41121P	A04			D41129J	4			ALL
0005	20		PA		11-7	22-11-11	D41121P	A05			D41129J	5			ALL
0006	20		PA		11-7	22-11-12	D41121P	A06			D41129J	6			ALL
0007	20		PA		11-7	22-11-12	D41121P	A07			D41129J	7			ALL
0008	22		PA		11-7	22-13-11	D41121P	A08			D41129J	8			ALL
0009	22		PA		11-7	22-13-11	D41121P	A09			D41129J	9			ALL
0010	20		PA		11-7	22-13-11	D41121P	A10			D41129J	10			ALL
0011	20		PA		11-7	22-13-11	D41121P	A11			D41129J	11			ALL
0012	20		PA		11-7	22-13-11	D41121P	A12			D41129J	12			ALL
0013	20		PA		11-7	22-13-11	D41121P	A13			D41129J	13			ALL
0014	20		PA		11-7	22-13-11	D41121P	A14			D41129J	14			ALL
0015	22		CQ		11-7	22-14-11	D41121P	A15			D41129J	15			ALL
0016	22		CQ		11-7	34-51-41	D41121P	B01			D41129J	19			YD160-YR328
0017	22		CQ		11-7	22-14-11	D41121P	A17			D41129J	17			ALL
0018	22		CQ		4-4	34-51-41	D41127J	2			D41129J	18			ALL
0021	22		CQ		4-4	22-11-18	D41127J	1			D41129J	16			ALL
0022	22		CQ		11-7	34-51-41	D41121P	A18			D41129J	20			ALL
0023	22		CQ		4-4	SPARE	D41127J	23			D41129J	23			ALL
0025	22		CQ		11-7	34-16-11	D41121P	B15			D41129J	25			ALL
0026	22		CQ		11-7	SPARE	D41121P	B16			D41129J	26			ALL
0028	22		PA		4-4	34-21-15	D41127J	8			D41129J	49			ALL
0030	22		PA		11-7	30-11-11	D41129J	46			D41121P	A16			ALL
0031	22		PA		11-7	22-13-11	D41121P	B09			D41129J	24			YD157-YR328
0050	22		PA		11-7	34-21-15	D41121P	A19			D41129J	50			ALL
0051	22		PA		11-7	34-21-15	D41121P	A20			D41129J	51			ALL
0052	22		PA		11-7	34-21-15	D41121P	B14			D41129J	52			ALL
0053	20		CQ		4-4	SPARE	D41129J	53			D41127J	13			ALL
0054	20		CQ		4-4	SPARE	D41129J	54			D41127J	14			ALL
0055	20		CQ		4-4	SPARE	D41129J	55			D41127J	15			ALL
1001	22		X1	A	11-7	22-11-11	D41121P	A01			D41129J	1			ALL
1001Z				A	0-0	22-11-11	D41121P	PERG	1F		D41129J	S/R			ALL
2001B	24		Y2	BA	11-7	34-33-11	D41129J	34			D41121P	B08			YD157-YR328
2001R	24		Y2	BA	0-0	34-33-11	D41129J	33			D41121P	B07			YD157-YR328
2001Z				BA	0-0	34-33-11	D41129J	S/R			D41121P	PERG	1F		YD157-YR328
2003B	24		Y2	C	11-7	34-21-13	D41129J	32			D41121P	B13			ALL
2003R	24		Y2	C	0-0	34-21-13	D41129J	31			D41121P	B12			ALL
2003Z				C	0-0	34-21-13	D41129J	S/R			D41121P	PERG	1F		ALL

WIRE LIST

D280A108

91-21-11

Section W5720

Page 1

Nov 12/2012



WIRE LIST
D280A108

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5723		286A5723			INTERRACK E1-4 TO E1-1,E1-2,E1-3 (continued)											
0006		24		PK		4-4	34-53-21	D41507J				D41131P	6			ALL
0007		24		PK		4-4	34-53-21	D41507J				D41131P	7			ALL
0008		24		PK		4-4	34-53-21	D41507J				D41131P	8			ALL
0009		24		PK		4-4	34-53-21	D41507J				D41131P	9			ALL
0010		24		PK		4-4	34-53-21	D41507J				D41131P	10			ALL
0011		24		PK		4-4	34-53-21	D41507J				D41131P	11			ALL
0012		24		PK		4-4	34-53-21	D41507J				D41131P	12			ALL
0013		24		PK		4-4	34-53-21	D41507J				D41131P	13			ALL
0014		24		PK		4-4	34-53-21	D41507J				D41131P	14			ALL
0015		24		PK		4-4	34-53-21	D41507J				D41131P	15			ALL
0016		24		PK		4-4	34-53-21	D41507J				D41131P	16			ALL
0017		24		PK		4-4	34-53-21	D41507J				D41131P	17			ALL
0018		24		PK		4-4	34-53-21	D41507J				D41131P	18			ALL
0019		24		PK		4-4	34-53-21	D41507J				D41131P	19			ALL
0020		24		PK		4-4	34-53-21	D41507J				D41131P	20			ALL
0021		24		PK		4-4	34-53-21	D41507J				D41131P	21			ALL
0022		24		PK		4-4	34-53-21	D41507J				D41131P	22			ALL
0023		24		PK		4-4	34-53-21	D41507J				D41131P	23			ALL
0024		24		PK		4-4	34-53-21	D41507J				D41131P	24			ALL
0025		24		PK		4-4	34-53-21	D41507J				D41131P	25			ALL
0031		22		PA		10-1	34-55-21	D40047J				D41507J	31			ALL
0032		20		PA		10-1	34-53-21	D40047J				D41507J	32			ALL
0034		20		PA		11-3	22-11-12	D40047J				D41131P	27			ALL
0042		22		CQ		6-11	22-13-11	D40047J				D43317P	A12			ALL
0043		22		CQ		6-11	22-13-11	D40047J				D43317P	A15			ALL
0045		22		CQ		6-11	22-14-11	D40047J				D43317P	B10			ALL
0046		20		CQ		6-11	22-14-11	D40047J				D43317P	B11			ALL
0055		22		CQ		6-11	22-11-11	D40047J				D43317P	A05			ALL
0064		22		PA		11-3	32-64-21	D41131P				D40047J	39			ALL
0074		20		CQ		6-11	SPARE	D40047J				D43317P	A09			YD158-YR328
0101		20		CQ		6-11	32-64-21	D40047J				D43317P	A01			ALL
0102		20		CQ		6-11	SPARE	D40047J				D43317P	A02			ALL
0103		20		CQ		6-11	SPARE	D40047J				D43317P	A03			ALL
0106		20		CQ		6-11	22-11-12	D40047J				D43317P	A06			ALL
0107		20		CQ		6-11	22-11-12	D40047J				D43317P	A07			ALL
0108		20		CQ		6-11	22-11-12	D40047J				D43317P	A08			ALL
0125		20		CQ		6-11	22-18-11	D40047J				D43317P	B12			ALL
0126		22		CQ		6-11	22-18-11	D40047J				D43317P	B13			ALL
0127		22		CQ		6-11	22-18-11	D40047J				D43317P	B14			ALL

WIRE LIST

D280A108

91-21-11

Section W5720

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To						
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W5723	286A5723				INTERRACK E1-4 TO E1-1,E1-2,E1-3 (continued)											
0128	22		CQ		6-11	22-18-11	D40047J		28			D43317P	B15			ALL
0129	22		CQ		6-11	22-18-11	D40047J		29			D43317P	B16			ALL
0133	22		CQ		6-11	22-18-11	D40047J		33			D43317P	B09			ALL
0140	22		CQ		6-10	22-11-18	D40063P		A10			D40047J	40			ALL
0144	20		CQ		6-10	22-11-11	D40063P		A04			D40047J	44			ALL
0145	20		CQ		6-10	22-11-11	D40063P		A05			D40047J	45			ALL
0146	20		CQ		6-10	22-11-11	D40063P		A06			D40047J	46			ALL
0147	20		CQ		6-11	22-11-11	D40047J		37			D43317P	B07			ALL
0148	20		CQ		6-11	22-11-11	D40047J		38			D43317P	B08			ALL
0151	20		CQ		6-10	SPARE	D40047J		51			D40063P	A01			YC051-YD157
1104	20		X1	AR	6-11	22-11-11	D40047J		4			D43317P	A04			ALL
1104Z				AR	0-0	22-11-11	D40047J		S/R			D43317P	PERG	1F		ALL
2004B	24		Y2	AD	4-0	SPARE	D41213J		13			D40047J	53			YC051-YD157
2004R	24		Y2	AD	0-0	SPARE	D41213J		12			D40047J	52			YC051-YD157
2004Z				AD	0-0	SPARE	D41213J		S/R			D40047J	S/R			YC051-YD157
2016B	24		Y2	BP	9-0	34-21-24	D41213J		17			D41507J	36			ALL
2016R	24		Y2	BP	0-0	34-21-24	D41213J		16			D41507J	35			ALL
2016Z				BP	0-0	34-21-24	D41213J		S/R			D41507J	S/R			ALL
2020B	22		X2	DB	10-1	34-53-21	D40047J		52			D41507J	52			YD158-YR328
2020R	22		X2	DB	0-0	34-53-21	D40047J		51			D41507J	51			YD158-YR328
2020Z				DB	0-0	34-53-21	D40047J		S/R			D41507J	S/R			YD158-YR328
2021B	24		Y2	CA	6-11	22-11-51	D40047J		11			D43317P	A11			YD157
2021B	24		Y2	DA	6-11	22-11-51	D40047J		11			D43317P	A11			YD158-YR328
2021R	24		Y2	CA	0-0	22-11-51	D40047J		10			D43317P	A10			YD157
2021R	24		Y2	DA	0-0	22-11-51	D40047J		10			D43317P	A10			YD158-YR328
2021Z				CA	0-0	22-11-51	D40047J		S/R			D43317P	PERG	1F		YD157
2021Z				DA	0-0	22-11-51	D40047J		S/R			D43317P	PERG	1F		YD158-YR328
2040B	24		Y2	AE	4-0	SPARE	D40047J		55			D41213J	15			ALL
2040R	24		Y2	AE	0-0	SPARE	D40047J		54			D41213J	14			ALL
2040Z				AE	0-0	SPARE	D40047J		S/R			D41213J	S/R			ALL
2049B	24		Y2	BW	6-10	73-24-21	D40063P		A08			D40047J	50			ALL
2049R	24		Y2	BW	0-0	73-24-21	D40063P		A07			D40047J	49			ALL
2049Z				BW	0-0	73-24-21	D40063P		PERG	1F		D40047J	S/R			ALL
2110B	22		X2	AI	6-11	22-11-31	D40047J		11			D43317P	A11			YC051-YD155
2110R	22		X2	AI	0-0	22-11-31	D40047J		10			D43317P	A10			YC051-YD155
2110Z				AI	0-0	22-11-31	D40047J		S/R			D43317P	PERG	1F		YC051-YD155
2112B	24		Y2	AJ	9-8	34-21-14	D41507J		34			D43317P	B02			ALL
2112R	24		Y2	AJ	0-0	34-21-14	D41507J		33			D43317P	B01			ALL
2112Z				AJ	0-0	34-21-14	D41507J		S/R			D43317P	PERG	1F		ALL

WIRE LIST

D280A108

91-21-11

Section W5720

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description		From				To					
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5723	286A5723			INTERRACK E1-4 TO E1-1,E1-2,E1-3 (continued)											
2113B	24	Y2	AK		6-11	22-11-51	D40047J		14		D43317P	A14			ALL
2113R	24	Y2	AK		0-0	22-11-51	D40047J		13		D43317P	A13			ALL
2113Z			AK		0-0	22-11-51	D40047J		S/R		D43317P	PERG	1F		ALL
2116B	24	Y2	AL		6-11	22-11-51	D40047J		17		D43317P	A17			ALL
2116R	24	Y2	AL		0-0	22-11-51	D40047J		16		D43317P	A16			ALL
2116Z			AL		0-0	22-11-51	D40047J		S/R		D43317P	PERG	1F		ALL
2119B	22	M2	AM		6-11	22-12-31	D40047J		19		D43317P	A19			YC051-YD155
2119R	22	M2	AM		0-0	22-12-31	D40047J		18		D43317P	A18			YC051-YD155
2119ZI			AM		0-0	22-12-31	D40047J		20		D43317P	A20			YC051-YD155
2119ZO			AM		0-0	22-12-31	D40047J		S/R		D43317P	PERG	1F		YC051-YD155
2122B	22	X2	AN		6-11	SPARE	D40047J		22		D43317P	B04			YC051-YC052
2122B	24	Y2	AN		6-11	34-58-21	D40047J		22		D43317P	B04			YC053-YR328
2122R	22	X2	AN		0-0	SPARE	D40047J		21		D43317P	B03			YC051-YC052
2122R	24	Y2	AN		0-0	34-58-21	D40047J		21		D43317P	B03			YC053-YR328
2122Z			AN		0-0	SPARE	D40047J		S/R		D43317P	PERG	1F		YC051-YC052
2122Z			AN		0-0	34-58-21	D40047J		S/R		D43317P	PERG	1F		YC053-YR328
2130B	22	X2	AO		6-11	22-18-11	D40047J		31		D43317P	B18			ALL
2130R	22	X2	AO		0-0	22-18-11	D40047J		30		D43317P	B17			ALL
2130Z			AO		0-0	22-18-11	D40047J		S/R		D43317P	PERG	1F		ALL
2135B	24	Y2	AP		6-11	34-31-21	D40047J		36		D43317P	B20			ALL
2135R	24	Y2	AP		0-0	34-31-21	D40047J		35		D43317P	B19			ALL
2135Z			AP		0-0	34-31-21	D40047J		S/R		D43317P	PERG	1F		ALL
2136B	24	Y2	AF		6-11	SPARE	D40047J		43		D43317P	B06			YC051-YC064
2136B	24	Y2	AF		6-11	34-31-21	D40047J		43		D43317P	B06			YC065-YR328
2136R	24	Y2	AF		0-0	SPARE	D40047J		42		D43317P	B05			YC051-YC064
2136R	24	Y2	AF		0-0	34-31-21	D40047J		42		D43317P	B05			YC065-YR328
2136Z			AF		0-0	SPARE	D40047J		S/R		D43317P	PERG	1F		YC051-YC064
2136Z			AF		0-0	34-31-21	D40047J		S/R		D43317P	PERG	1F		YC065-YR328
2501B	24	Y2	CA		28-3	23-27-37	D41507J		40		D43333P	B09			YD158-YN260
2501R	24	Y2	CA		0-0	23-27-37	D41507J		39		D43333P	A09			YD158-YN260
2501Z			CA		0-0	23-27-37	D41507J		S/R		D43333P	PERG	1F		YD158-YN260
2502B	24	Y2	CB		28-3	SPARE	D41507J		42		D43333P	B08			YD158-YD170
2502B	24	Y2	CB		28-3	34-45-21	D41507J		42		D43333P	B08			YL951-YR328
2502R	24	Y2	CB		0-0	SPARE	D41507J		41		D43333P	A08			YD158-YD170
2502R	24	Y2	CB		0-0	34-45-21	D41507J		41		D43333P	A08			YL951-YR328
2502Z			CB		0-0	SPARE	D41507J		S/R		D43333P	PERG	1F		YD158-YD170
2502Z			CB		0-0	34-45-21	D41507J		S/R		D43333P	PERG	1F		YL951-YR328
2503B	24	Y2	CC		28-3	SPARE	D41507J		44		D43333P	B10			YD158-YR328
2503R	24	Y2	CC		0-0	SPARE	D41507J		43		D43333P	A10			YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W5720

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W5723	286A5723				INTERRACK E1-4 TO E1-1,E1-2,E1-3 (continued)											
2503Z				CC	0-0	SPARE		D41507J		S/R		D43333P	PERG	1F		YD158-YR328
2504B	24		Y2	CD	28-3	23-27-37		D41507J		46		D43333P	B05			YD158-YR328
2504R	24		Y2	CD	0-0	23-27-37		D41507J		45		D43333P	A05			YD158-YR328
2504Z				CD	0-0	23-27-37		D41507J		S/R		D43333P	PERG	1F		YD158-YR328
2505B	24		Y2	CE	28-3	23-27-37		D41507J		50		D43333P	B06			YD158-YR328
2505R	24		Y2	CE	0-0	23-27-37		D41507J		49		D43333P	A06			YD158-YR328
2505Z				CE	0-0	23-27-37		D41507J		S/R		D43333P	PERG	1F		YD158-YR328
2506B	24		Y2	CF	28-3	SPARE		D41507J		48		D43333P	B07			YD158-YR328
2506R	24		Y2	CF	0-0	SPARE		D41507J		47		D43333P	A07			YD158-YR328
2506Z				CF	0-0	SPARE		D41507J		S/R		D43333P	PERG	1F		YD158-YR328
2509B	24		Y2	CI	31-11	23-27-37		D41131P		29		D43306P	B01			YD158-YR328
2509R	24		Y2	CI	0-0	23-27-37		D41131P		28		D43306P	A01			YD158-YR328
2509Z				CI	0-0	23-27-37		D41131P		30		D43306P	PERG	1F		YD158-YR328
2510B	24		Y2	CJ	31-11	23-27-37		D41131P		32		D43306P	B02			YD158-YR328
2510R	24		Y2	CJ	0-0	23-27-37		D41131P		31		D43306P	A02			YD158-YR328
2510Z				CJ	0-0	23-27-37		D41131P		33		D43306P	PERG	1F		YD158-YR328
2511B	24		Y2	CK	31-11	SPARE		D41131P		35		D43306P	B03			YD158-YR328
2511R	24		Y2	CK	0-0	SPARE		D41131P		34		D43306P	A03			YD158-YR328
2511Z				CK	0-0	SPARE		D41131P		36		D43306P	PERG	1F		YD158-YR328
2512B	24		Y2	CL	24-4	SPARE		D43306P		B04		D41213J		4		YD158-YR328
2512R	24		Y2	CL	0-0	SPARE		D43306P		A04		D41213J		3		YD158-YR328
2512Z				CL	0-0	SPARE		D43306P		PERG	1F	D41213J		S/R		YD158-YR328
2513B	24		Y2	CM	24-4	23-27-37		D43306P		B05		D41213J		2		YD158-YN260
2513R	24		Y2	CM	0-0	23-27-37		D43306P		A05		D41213J		1		YD158-YN260
2513Z				CM	0-0	23-27-37		D43306P		PERG	1F	D41213J		S/R		YD158-YN260
W5726	286A5726				LRU ECU TO APU FIREWALL AND E/E BAY											
0001	18		HA		18-11	33-35-11		D44584P		1		SM00001		9		YC051-YC052
0001	18		PA		4-1	33-35-11		D40854P		3	18	SM00001		9		YC053-YL954, YN231-YN235
0001	18		PA		4-1	33-35-11		D40854P		53	18	SM00001		9		YL955-YL999, YN236-YR328
0002	18		HA		17-2	33-35-11		D44584P		2		GD00060	AC..	1		YC051-YC052
0003	20		PA		132-5	33-44-12		D40912P		A04		D44584P		3		YC051-YC052
0003	20		PA		115-3	33-44-12		D40912P		A04		D40854P		6		YC053-YC055
0003	20		PA		115-9	33-44-12		D40912P		A04		D40854P		6		YC056-YL999, YR301-YR328
0003	20		PA		96-11	33-44-12		D40912P		A04		D40854P		6		YN231-YN501
0004	20		PA		17-2	33-44-12		GD00060		AC..	1	D44584P		4		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W5720

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5726	286A5726			LRU ECU TO APU FIREWALL AND E/E BAY (continued)											
0011	18		HA		16-5	33-35-11	SP04010		S		SM00001		9		YC051-YC052
0011	18		PA		4-5	33-35-11	SP04010		S		SM00001		9		YC053-YL999, YR301-YR328
0011	18		PA		4-4	33-35-11	SP04010		S		SM00001		9		YN231-YN501
0021	18		HA		6-8	33-35-11	S00087	1	G7		SM00001		9		YC051-YC052
0021	18		PA		4-1	33-35-11	D40854P	4	18		SM00001		9		YC053-YL954, YN231-YN235
0021	20		PA		4-1	33-35-11	D40854P	4			SM00001		9		YL955-YL999, YN236-YR328
0022	18		HA		6-8	33-35-11	S00087	2	G7		SM00002		9		YC051-YC052
0023	18		HA		14-6	33-35-11	L00015	=P	BK		SM00002		9		YC051-YC052
0024	18		HA		9-7	33-35-11	L00016	=P	BK		SM00002		9		YC051-YC052
0025	18		HA		8-3	33-35-11	L00015	=G	G7		GD00048	AC..	1		YC051-YC052
0026	18		HA		13-7	33-35-11	L00016	=G	G7		GD00048	AC..	1		YC051-YC052
0032	18		HA		10-0	33-35-11	D40060J	5			SM00001		9		YC051-YC052
0032	18		PA		4-1	33-35-11	D40854P	5	18		SM00001		9		YC053-YL954, YN231-YN235
0032	20		PA		4-1	33-35-11	D40854P	5			SM00001		9		YL955-YL999, YN236-YR328
0034	18		HA		2-4	33-35-11	D40060J	6			GD00046	AC..	1		YC051-YC052
0036	18		HA		2-4	33-35-11	D40060J	7			GD00046	AC..	1		YC051-YC052
0501	24		PK		112-1	49-41-11	D40928P	A03			D03599B	B09			YC051-YC055
0501	24		PK		112-7	49-41-11	D40928P	A03			D03599B	B09			YC056-YL999, YR301-YR328
0501	24		PK		94-2	49-41-11	D40928P	A03			D03599B	B09			YN231-YN501
0502	24		PK		112-1	49-41-11	D40928P	B03			D03599B	D01			YC051-YC055
0502	24		PK		112-7	49-41-11	D40928P	B03			D03599B	D01			YC056-YL999, YR301-YR328
0502	24		PK		94-2	49-41-11	D40928P	B03			D03599B	D01			YN231-YN501
0503	24		PK		112-1	49-41-11	D40928P	A04			D03599B	D02			YC051-YC055
0503	24		PK		112-7	49-41-11	D40928P	A04			D03599B	D02			YC056-YL999, YR301-YR328
0503	24		PK		94-2	49-41-11	D40928P	A04			D03599B	D02			YN231-YN501
0504	24		PK		112-1	49-41-11	D40928P	B04			D03599B	D03			YC051-YC055
0504	24		PK		112-7	49-41-11	D40928P	B04			D03599B	D03			YC056-YL999, YR301-YR328
0504	24		PK		94-2	49-41-11	D40928P	B04			D03599B	D03			YN231-YN501
0505	24		PK		112-3	49-41-11	D40928P	A05			D03599A	C13			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5720

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5726	286A5726				LRU ECU TO APU FIREWALL AND E/E BAY (continued)										
0505	24		PK		112-8	49-41-11	D40928P	A05			D03599A	C13			YC056-YL999, YR301-YR328
0505	24		PK		94-2	49-41-11	D40928P	A05			D03599A	C13			YN231-YN501
0507	24		PK		112-4	49-52-31	D40908P	A01			D03599B	A06			YC051-YC055, YD158-YL954
0507	24		PK		112-6	49-52-31	D40908P	A01			D03599B	A06			YC056-YD157, YL955-YL999, YR301-YR328
0507	24		PK		94-2	49-52-31	D40908P	A01			D03599B	A06			YN231-YN501
0508	24		PK		113-5	49-52-31	D40904P	A01			D03599B	C04			YC051-YC055
0508	24		PK		114-3	49-52-31	D40904P	A01			D03599B	C04			YC056-YL999, YR301-YR328
0508	24		PK		95-10	49-52-31	D40904P	A01			D03599B	C04			YN231-YN501
0509	24		PK		113-5	49-52-31	D40904P	B01			D03599B	B06			YC051-YC055
0509	24		PK		114-3	49-52-31	D40904P	B01			D03599B	B06			YC056-YL999, YR301-YR328
0509	24		PK		95-10	49-52-31	D40904P	B01			D03599B	B06			YN231-YN501
0510	24		PK		113-5	49-52-31	D40904P	A02			D03599B	B05			YC051-YC055
0510	24		PK		114-3	49-52-31	D40904P	A02			D03599B	B05			YC056-YL999, YR301-YR328
0510	24		PK		95-10	49-52-31	D40904P	A02			D03599B	B05			YN231-YN501
0511	24		PK		7-7	49-52-31	GD00654	DC..	1		D03599B	C07			YN231-YN501
0512	24		PK		114-1	49-52-31	D40912P	B07			D03599B	A01			YC051-YC055
0512	24		PK		114-6	49-52-31	D40912P	B07			D03599B	A01			YC056-YL999, YR301-YR328
0512	24		PK		96-2	49-52-31	D40912P	B07			D03599B	A01			YN231-YN501
0513	24		PK		113-5	49-52-31	D40904P	B02			D03599B	C03			YC051-YC055
0513	24		PK		114-3	49-52-31	D40904P	B02			D03599B	C03			YC056-YL999, YR301-YR328
0513	24		PK		95-10	49-52-31	D40904P	B02			D03599B	C03			YN231-YN501
0514	22		PA		49-8	49-52-31	D03599B	B10			D10434	5			YC051-YC052
0514	22		PA		35-3	49-52-31	D03599B	B10			D40854P	9			YC053-YL999, YR301-YR328
0514	22		PA		35-4	49-52-31	D03599B	B10			D40854P	9			YN231-YN501
0515	20		HA		2-4	49-52-31	GD01240	DC..	1		D10434	1			YC051-YC052
0516	22		PA		0-7	49-52-31	D03599B	C09			SM00013		9		ALL
0517	20		HA		2-4	49-52-31	GD01240	DC..	1		D10434	4			YC051-YC052
0519	22		CQ		0-7	49-62-11	D03599B	B01			SM00016		S		ALL
0520	22		CQ		112-1	49-62-11	D03599B	B03			D40928P	B10			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W5720

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W5726	286A5726				LRU ECU TO APU FIREWALL AND E/E BAY (continued)											
0520	22		CQ		112-7	49-62-11		D03599B	B03			D40928P	B10			YC056-YL999, YR301-YR328
0520	22		CQ		94-2	49-62-11		D03599B	B03			D40928P	B10			YN231-YN501
0521	22		CQ		114-2	49-62-11		D40946P	A02			D03599B	C01			YC051-YC055
0521	22		CQ		114-7	49-62-11		D40946P	A02			D03599B	C01			YC056-YL999, YR301-YR328
0521	22		CQ		96-3	49-62-11		D40946P	A02			D03599B	C01			YN231-YN501
0522	22		HA		113-5	49-52-31		SM00013		9		D40904P	A03			YC051-YC052
0522	22		PA		113-5	49-52-31		SM00013		9		D40904P	A03			YC053-YC055
0522	22		PA		114-3	49-52-31		SM00013		9		D40904P	A03			YC056-YL999, YR301-YR328
0522	22		PA		95-10	49-52-31		SM00013		9		D40904P	A03			YN231-YN501
0525	22		PA		110-2	49-62-11		D40926P	A01			D03599B	A13			YC051-YC055
0525	22		PA		110-7	49-62-11		D40926P	A01			D03599B	A13			YC056-YL999, YR301-YR328
0525	22		PA		92-3	49-62-11		D40926P	A01			D03599B	A13			YN231-YN501
0526	22		PA		110-2	49-62-11		D40926P	B01			D03599B	B11			YC051-YC055
0526	22		PA		110-7	49-62-11		D40926P	B01			D03599B	B11			YC056-YL999, YR301-YR328
0526	22		PA		92-3	49-62-11		D40926P	B01			D03599B	B11			YN231-YN501
0527	22		PA		110-2	49-62-11		D40926P	A02			D03599B	A15			YC051-YC055
0527	22		PA		110-7	49-62-11		D40926P	A02			D03599B	A15			YC056-YL999, YR301-YR328
0527	22		PA		92-3	49-62-11		D40926P	A02			D03599B	A15			YN231-YN501
0528	22		CQ		114-2	49-62-11		D40946P	A01			D03599B	B02			YC051-YC055
0528	22		CQ		114-7	49-62-11		D40946P	A01			D03599B	B02			YC056-YL999, YR301-YR328
0528	22		CQ		96-3	49-62-11		D40946P	A01			D03599B	B02			YN231-YN501
0529	22		PA		112-5	49-62-11		D40908P	B01			D03599A	A03			YC051-YC055
0529	22		PA		112-7	49-62-11		D40908P	B01			D03599A	A03			YC056-YD157, YL955-YL999, YR301-YR328
0529	22		PA		112-6	49-62-11		D40908P	B01			D03599A	A03			YD158-YL954
0529	22		PA		94-2	49-62-11		D40908P	B01			D03599A	A03			YN231-YN501
0530	22		PA		47-2	49-62-11		D03599B	A10			D01246	1			YC051-YC052
0530	22		PA		34-8	49-62-11		D03599B	A10			D40790P	9			YC053-YL999, YR301-YR328
0530	22		PA		34-9	49-62-11		D03599B	A10			D40790P	9			YN231-YN501
0531	22		PA		47-2	49-62-11		D03599B	A04			D01246	2			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W5720

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5726	286A5726				LRU ECU TO APU FIREWALL AND E/E BAY (continued)										
0531	22		PA		34-8	49-62-11	D03599B	A04			D40790P	21			YC053-YL999, YR301-YR328
0531	22		PA		34-9	49-62-11	D03599B	A04			D40790P	21			YN231-YN501
0532	22		PA		47-2	49-62-11	D03599B	A03			D01246	4			YC051-YC052
0532	22		PA		34-8	49-62-11	D03599B	A03			D40790P	22			YC053-YL999, YR301-YR328
0532	22		PA		34-9	49-62-11	D03599B	A03			D40790P	22			YN231-YN501
0533	22		PA		0-7	49-62-11	D03599B	A08			SM00003		9		ALL
0534	20		PA		46-3	49-62-11	SM00003		9		D00922	1			YC051-YC052
0534	20		PA		34-8	49-62-11	SM00003		9		D40790P	34			YC053-YL999, YR301-YR328
0534	20		PA		34-9	49-62-11	SM00003		9		D40790P	34			YN231-YN501
0535	20		PA		3-1	49-62-11	D00922		3		GD00048	DC..	1		YC051-YC052
0536	22		PA		0-7	49-62-11	D03599B	A07			SM00004		9		ALL
0537	20		PA		46-3	49-62-11	SM00004		9		D00922	2			YC051-YC052
0537	20		PA		34-8	49-62-11	SM00004		9		D40790P	40			YC053-YL999, YR301-YR328
0537	20		PA		34-9	49-62-11	SM00004		9		D40790P	40			YN231-YN501
0538	22		PA		3-3	49-62-11	D03599B	B08			SP00252		S		YC051-YL999, YR301-YR328
0538	22		PA		2-8	49-62-11	D03599B	B08			SP00252		S		YN231-YN501
0540	22		PA		3-3	49-62-11	D03599B	D05			SP00254		S		YC051-YL999, YR301-YR328
0540	22		PA		2-8	49-62-11	D03599B	D05			SP00254		S		YN231-YN501
0542	22		PA		3-3	49-62-11	D03599B	D09			SP00256		S		YC051-YL999, YR301-YR328
0542	22		PA		2-8	49-62-11	D03599B	D09			SP00256		S		YN231-YN501
0544	22		PA		3-3	49-62-11	D03599B	B07			SP00258		S		YC051-YL999, YR301-YR328
0544	22		PA		2-8	49-62-11	D03599B	B07			SP00258		S		YN231-YN501
0546	22		HA		48-7	49-62-12	D03599A	C01			D10436	18			YC051-YC052
0546	22		PA		35-4	49-62-12	D03599A	C01			D40854P	25			YC053-YR328
0547	22		HA		48-7	49-62-12	D03599A	D01			D10436	32			YC051-YC052
0547	22		PA		35-4	49-62-12	D03599A	D01			D40854P	26			YC053-YR328
0548	22		HA		48-6	49-62-12	D03599B	C10			D10436	27			YC051-YC052
0548	22		PA		35-3	49-62-12	D03599B	C10			D40854P	34			YC053-YL999, YR301-YR328
0548	22		PA		35-4	49-62-12	D03599B	C10			D40854P	34			YN231-YN501
0549	20		HA		2-0	49-62-12	D10436		42		GD01240	DC..	1		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W5720

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W5726	286A5726	LRU ECU TO APU FIREWALL AND E/E BAY (continued)													
0553	22	HA	49-8	49-62-51	D03599B	D10			D10434	18				YC051-YC052	
0553	22	PA	35-3	49-62-51	D03599B	D10			D40854P	49				YC053-YL999, YR301-YR328	
0553	22	PA	35-4	49-62-51	D03599B	D10			D40854P	49				YN231-YN501	
0554	16	HA	7-4	49-62-51	D03599C	3			GD00654	DC..	1			YC051-YC052	
0554	16	PA	7-4	49-62-51	D03599C	3			GD00654	DC..	1			YC053-YL999, YR301-YR328	
0554	16	PA	7-7	49-62-51	D03599C	3			GD00654	DC..	1			YN231-YN501	
0555	16	HA	7-4	49-62-51	D03599C	4			GD00654	ST..	1			YC051-YC052	
0555	16	PA	7-4	49-62-51	D03599C	4			GD00654	ST..	1			YC053-YL999, YR301-YR328	
0555	16	PA	7-7	49-62-51	D03599C	4			GD00654	ST..	1			YN231-YN501	
0556	20	HA	7-4	49-62-51	D03599C	PERG	1A		GD00654	ST..	1			YC051-YC052	
0556	20	PA	7-4	49-62-51	D03599C	PERG	1A		GD00654	ST..	1			YC053-YL999, YR301-YR328	
0556	20	PA	7-7	49-62-51	D03599C	PERG	1A		GD00654	ST..	1			YN231-YN501	
0557	22	PA	110-2	49-94-21	D03599B	A14			D40926P	B02				YC051-YC055	
0557	22	PA	110-7	49-94-21	D03599B	A14			D40926P	B02				YC056-YL999, YR301-YR328	
0557	22	PA	92-3	49-94-21	D03599B	A14			D40926P	B02				YN231-YN501	
0558	22	PA	110-2	49-94-21	D03599B	A12			D40926P	A03				YC051-YC055	
0558	22	PA	110-7	49-94-21	D03599B	A12			D40926P	A03				YC056-YL999, YR301-YR328	
0558	22	PA	92-3	49-94-21	D03599B	A12			D40926P	A03				YN231-YN501	
0559	22	HA	49-8	49-94-21	D03599B	B04			D10434	11				YC051-YC052	
0559	22	PA	35-3	49-94-21	D03599B	B04			D40854P	50				YC053-YL999, YR301-YR328	
0559	22	PA	35-4	49-94-21	D03599B	B04			D40854P	50				YN231-YN501	
0560	20	HA	2-4	49-94-21	D10434	12			GD01240	DC..	1			YC051-YC052	
0561	22	HA	49-8	49-94-21	D03599B	C06			D10434	22				YC051-YC052	
0561	22	PA	35-3	49-94-21	D03599B	C06			D40854P	51				YC053-YL999, YR301-YR328	
0561	22	PA	35-4	49-94-21	D03599B	C06			D40854P	51				YN231-YN501	
0562	22	HA	49-8	49-94-21	D03599B	C05			D10434	9				YC051-YC052	
0562	22	PA	35-3	49-94-21	D03599B	C05			D40854P	52				YC053-YL999, YR301-YR328	
0562	22	PA	35-4	49-94-21	D03599B	C05			D40854P	52				YN231-YN501	
0563	20	HA	2-4	49-94-21	D10434	19			GD01240	DC..	1			YC051-YC052	
0564	22	HA	49-8	49-52-31	SM00013		9		D10434	3				YC051-YC052	

WIRE LIST

D280A108

91-21-11

Section W5720

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5726	286A5726			LRU ECU TO APU FIREWALL AND E/E BAY (continued)											
0564	22	PA			35-3	49-52-31	SM00013			9	D40854P	10			YC053-YL999, YR301-YR328
0564	22	PA			35-4	49-52-31	SM00013			9	D40854P	10			YN231-YN501
0566	22	PA			3-5	24-21-31	D40942P	A01			D40926P	A04			ALL
0567	22	PA			3-5	24-21-31	D40942P	B01			D40926P	B04			ALL
0568	22	PA			3-5	24-21-31	D40942P	A02			D40926P	A05			ALL
0569	20	PA			4-4	24-51-11	D11436	2			GD00918	DC..	E		ALL
0570	24	PK			110-2	24-28-41	D03599B	A11			D40926P	B05			YC051-YC055
0570	24	PK			110-7	24-28-41	D03599B	A11			D40926P	B05			YC056-YL999, YR301-YR328
0570	24	PK			92-3	24-28-41	D03599B	A11			D40926P	B05			YN231-YN501
0571	22	PA			4-4	24-22-31	D11436	24			D40926P	A06			ALL
0572	22	PA			4-4	24-22-31	D11436	9			D40926P	B06			ALL
0574	22	PA			49-8	49-62-12	D03599B	A09			D10434	25			YC051-YC052
0574	22	PA			35-3	49-62-12	D03599B	A09			D40854P	33			YC053-YL999, YR301-YR328
0574	22	PA			35-4	49-62-12	D03599B	A09			D40854P	33			YN231-YN501
0575	22	HA			2-4	49-62-12	D10434	26			GD01240	DC..	1		YC051-YC052
0576	22	HA			49-8	49-62-51	D03599B	D04			D10434	7			YC051-YC052
0576	22	PA			35-3	49-62-51	D03599B	D04			D40854P	48			YC053-YL999, YR301-YR328
0576	22	PA			35-4	49-62-51	D03599B	D04			D40854P	48			YN231-YN501
0577	16	PA			4-5	25-51-21	D11438	2			D40254P	F			YC051-YL999, YR301-YR328
0577	16	PA			4-5	SPARE	D11438	2			D40254P	F			YN231-YN501
0578	16	PA			4-5	25-51-21	D11438	3			D40254P	G			YC051-YL999, YR301-YR328
0578	16	PA			4-5	SPARE	D11438	3			D40254P	G			YN231-YN501
0579	16	PA			4-5	25-51-21	D11438	4			D40254P	H			YC051-YL999, YR301-YR328
0579	16	PA			4-5	SPARE	D11438	4			D40254P	H			YN231-YN501
0583	24	B6			5-5	31-62-14	D40912P	B04			D40926P	A10			ALL
0584	20	CQ			90-2	49-62-11	SP00028		S		SM00016		S		YC051-YL999, YR301-YR328
0584	20	CQ			71-1	49-62-11	SP00028		S		SM00016		S		YN231-YN501
0587	22	HA			2-4	49-62-12	D10434	27			GD01240	ST..	1		YC051-YC052
0588	22	HA			49-10	49-94-21	D10434	29			D03599A	C12			YC051-YC052
0588	22	PA			35-4	49-94-21	D40854P	54			D03599A	C12			YC053-YR328
0589	20	HA			2-4	49-94-21	D10434	13			GD01240	DC..	1		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W5720

Page 12

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W5726	286A5726				LRU ECU TO APU FIREWALL AND E/E BAY (continued)										
0590	22		HA		2-4	49-94-21	D10434		14		GD01240	ST..	1		YC051-YC052
0592	16		CQ		0-7	49-62-11	D03599C		2		SM00020		S		ALL
0593	20		PA		5-2	38-32-12	D40910P		B06		D40946P	B10			ALL
0594	18		PA		5-2	38-32-12	D40910P		K		D40946P		K		ALL
0595	24		PK		5-5	31-62-14	D40926P		B03		D40912P	A07			ALL
0597	22		PA		4-5	25-51-21	D11438		7		D40254P	A01			YC051-YL999, YR301-YR328
0597	22		PA		4-5	SPARE	D11438		7		D40254P	A01			YN231-YN501
0598	10		CQ		89-1	49-62-11	SP00030			S	SM00020			S	YC051-YL999, YR301-YR328
0598	10		CQ		70-1	49-62-11	SP00030			S	SM00020			S	YN231-YN501
0599	20		CQ		5-1	49-62-11	D40254P		A04		D40946P	A05			ALL
0600	22		CQ		110-6	49-62-11	D40254P		A02		D03599B	C02			YC051-YC055
0600	22		CQ		110-11	49-62-11	D40254P		A02		D03599B	C02			YC056-YL999, YR301-YR328
0600	22		CQ		92-7	49-62-11	D40254P		A02		D03599B	C02			YN231-YN501
0601	22		CQ		110-6	49-62-11	D40254P		A03		D03599B	A02			YC051-YC055
0601	22		CQ		110-11	49-62-11	D40254P		A03		D03599B	A02			YC056-YL999, YR301-YR328
0601	22		CQ		92-7	49-62-11	D40254P		A03		D03599B	A02			YN231-YN501
1101R	18		H9	BN	27-8	26-11-31	M01925		T/1	GW	D40060J		2		YC051-YC052
1101Z				BN	0-0	26-11-31	M01925		DED		D40060J	DED			YC051-YC052
1103R	20		H9	BQ	128-6	26-21-11	D40912P		A01		D01176		2		YC051-YC052
1103R	20		X5	BQ	114-9	26-21-11	D40912P		A01		D40790P		43		YC053-YC055
1103R	20		X5	BQ	115-2	26-21-11	D40912P		A01		D40790P		43		YC056-YL999, YR301-YR328
1103R	20		X5	BQ	96-5	26-21-11	D40912P		A01		D40790P		43		YN231-YN501
1103Z				BQ	0-0	26-21-11	D40912P		DED		D01176	DED			YC051-YC052
1103Z				BQ	0-0	26-21-11	D40912P		DED		D40790P	DED			YC053-YR328
1104R	18		H9	BR	3-7	26-21-11	D01176		1		GD01240	DC..	1		YC051-YC052
1104Z				BR	0-0	26-21-11	D01176		DED		GD01240	DED			YC051-YC052
1105R	20		H9	BS	127-9	26-21-11	D00594		4		D40912P	B01			YC051-YC052
1105R	20		X5	BS	114-9	26-21-11	D40790P		20		D40912P	B01			YC053-YC055
1105R	20		X5	BS	115-2	26-21-11	D40790P		20		D40912P	B01			YC056-YL999, YR301-YR328
1105R	20		X5	BS	96-5	26-21-11	D40790P		20		D40912P	B01			YN231-YN501
1105Z				BS	0-0	26-21-11	D00594		DED		D40912P	DED			YC051-YC052
1105Z				BS	0-0	26-21-11	D40790P		DED		D40912P	DED			YC053-YR328
1106R	18		H9	BT	2-10	26-21-11	D00594		5		GD01240	ST..	1		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W5720

Page 13

Nov 12/2012



WIRE LIST
D280A108

91-21-11
Section W5720
Page 14
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W5726	286A5726			LRU ECU TO APU FIREWALL AND E/E BAY (continued)										
2203B	22	HF	KC	130-8	49-41-11	D40928P	A09			D11118	27			YC051-YC052
2203B	22	X2	KC	112-9	49-41-11	D40928P	A09			D40790P	12			YC053-YC055
2203B	22	X2	KC	113-2	49-41-11	D40928P	A09			D40790P	12			YC056-YL999, YR301-YR328
2203B	22	X2	KC	94-5	49-41-11	D40928P	A09			D40790P	12			YN231-YN501
2203R	22	HF	KC	0-0	49-41-11	D40928P	B08			D11118	12			YC051-YC052
2203R	22	X2	KC	0-0	49-41-11	D40928P	B08			D40790P	13			YC053-YR328
2203Z			KC	0-0	49-41-11	D40928P	B09			D11118	26			YC051-YC052
2203Z			KC	0-0	49-41-11	D40928P	B09			D40790P	27	18		YC053-YR328
2204B	20	HF	KD	49-8	49-41-11	SM00015		9		D10434	16			YC051-YC052
2204B	20	X2	KD	35-3	49-41-11	SM00015		9		D40854P	7			YC053-YL999, YR301-YR328
2204B	20	X2	KD	35-4	49-41-11	SM00015		9		D40854P	7			YN231-YN501
2204R	20	HF	KD	0-0	49-41-11	SM00014		9		D10434	17			YC051-YC052
2204R	20	X2	KD	0-0	49-41-11	SM00014		9		D40854P	8			YC053-YR328
2204Z			KD	0-0	49-41-11	D03599B	PERG	1A		D10434	6			YC051-YC052
2204Z			KD	0-0	49-41-11	D03599B	PERG	1A		D40854P	S/R			YC053-YR328
2205B	22	HF	KE	48-7	49-52-31	D03599A	B14			D10436	21			YC051-YC052
2205B	22	X2	KE	35-4	49-52-31	D03599A	B14			D40854P	11			YC053-YR328
2205R	22	HF	KE	0-0	49-52-31	D03599A	B15			D10436	8			YC051-YC052
2205R	22	X2	KE	0-0	49-52-31	D03599A	B15			D40854P	12			YC053-YR328
2205Z			KE	0-0	49-52-31	D03599A			AA	D10436			AB	YC051-YC052
2205Z			KE	0-0	49-52-31	D03599A			AA	D40854P	S/R			YC053-YR328
2206B	22	HF	KF	48-7	49-52-31	D03599A	A14			D10436	22			YC051-YC052
2206B	22	X2	KF	35-4	49-52-31	D03599A	A14			D40854P	16			YC053-YR328
2206R	22	HF	KF	0-0	49-52-31	D03599A	A15			D10436	9			YC051-YC052
2206R	22	X2	KF	0-0	49-52-31	D03599A	A15			D40854P	17			YC053-YR328
2206Z			KF	0-0	49-52-31	D03599A			AA	D10436			AB	YC051-YC052
2206Z			KF	0-0	49-52-31	D03599A			AA	D40854P	S/R			YC053-YR328
2207B	22	HF	KG	48-7	49-52-31	D03599A	A11			D10436	5			YC051-YC052
2207B	22	X2	KG	35-4	49-52-31	D03599A	A11			D40854P	18			YC053-YR328
2207R	22	HF	KG	0-0	49-52-31	D03599A	A12			D10436	1			YC051-YC052
2207R	22	X2	KG	0-0	49-52-31	D03599A	A12			D40854P	19			YC053-YR328
2207Z			KG	0-0	49-52-31	D03599A			AC	D10436			AD	YC051-YC052
2207Z			KG	0-0	49-52-31	D03599A			AC	D40854P	S/R			YC053-YR328
2208B	22	HF	KH	48-7	49-52-31	D03599A	A10			D10436	15			YC051-YC052
2208B	22	X2	KH	35-4	49-52-31	D03599A	A10			D40854P	24			YC053-YR328
2208R	22	HF	KH	0-0	49-52-31	D03599A	B10			D10436	30			YC051-YC052
2208R	22	X2	KH	0-0	49-52-31	D03599A	B10			D40854P	43			YC053-YR328

WIRE LIST

D280A108

91-21-11

Section W5720

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5726		286A5726			LRU ECU TO APU FIREWALL AND E/E BAY (continued)											
2208Z					KH	0-0	49-52-31	D03599A			AC	D10436			AD	YC051-YC052
2208Z					KH	0-0	49-52-31	D03599A			AC	D40854P	S/R			YC053-YR328
2209B	22	HF			KI	50-1	49-52-31	D03599A	D10			D10912	23			YC051-YC052
2209B	22	X2			KI	34-9	49-52-31	D03599A	D10			D40790P	14			YC053-YR328
2209R	22	HF			KI	0-0	49-52-31	D03599A	D09			D10912	9			YC051-YC052
2209R	22	X2			KI	0-0	49-52-31	D03599A	D09			D40790P	15			YC053-YR328
2209Z					KI	0-0	49-52-31	D03599A	PERG	1A		D10912	22			YC051-YC052
2209Z					KI	0-0	49-52-31	D03599A	PERG	1A		D40790P	S/R			YC053-YR328
2210B	22	HF			KJ	50-1	49-52-31	D03599A	D08			D10912	10			YC051-YC052
2210B	22	X2			KJ	34-9	49-52-31	D03599A	D08			D40790P	17			YC053-YR328
2210R	22	HF			KJ	0-0	49-52-31	D03599A	C08			D10912	2			YC051-YC052
2210R	22	X2			KJ	0-0	49-52-31	D03599A	C08			D40790P	35			YC053-YR328
2210Z					KJ	0-0	49-52-31	D03599A	PERG	1A		D10912	3			YC051-YC052
2210Z					KJ	0-0	49-52-31	D03599A	PERG	1A		D40790P	S/R			YC053-YR328
2211B	22	HF			KK	50-1	49-52-31	D03599A	D11			D10912	21			YC051-YC052
2211B	22	X2			KK	34-9	49-52-31	D03599A	D11			D40790P	36			YC053-YR328
2211R	22	HF			KK	0-0	49-52-31	D03599A	C11			D10912	8			YC051-YC052
2211R	22	X2			KK	0-0	49-52-31	D03599A	C11			D40790P	37			YC053-YR328
2211Z					KK	0-0	49-52-31	D03599A	PERG	1A		D10912	20			YC051-YC052
2211Z					KK	0-0	49-52-31	D03599A	PERG	1A		D40790P	S/R			YC053-YR328
2212B	22	PB			KL	110-4	49-62-11	D40926P	B07			D03599A	C09			YC051-YC055
2212B	22	PB			KL	110-9	49-62-11	D40926P	B07			D03599A	C09			YC056-YL999, YR301-YR328
2212B	22	PB			KL	92-3	49-62-11	D40926P	B07			D03599A	C09			YN231-YN501
2212R	22	PB			KL	0-0	49-62-11	D40926P	A07			D03599A	B07			ALL
2213B	22	X2			KM	112-4	49-62-11	D03599B	D15			D40908P	B02			YC051-YC055, YD158-YL954
2213B	22	X2			KM	112-6	49-62-11	D03599B	D15			D40908P	B02			YC056-YD157, YL955-YL999, YR301-YR328
2213B	22	X2			KM	94-2	49-62-11	D03599B	D15			D40908P	B02			YN231-YN501
2213R	22	X2			KM	0-0	49-62-11	D03599B	C15			D40908P	A02			ALL
2213Z					KM	0-0	49-62-11	D03599B	PERG	1A		D40908P	PERG	1F		ALL
2214B	22	HF			KN	48-6	49-62-12	D03599B	D13			D10436	34			YC051-YC052
2214B	22	X2			KN	35-3	49-62-12	D03599B	D13			D40854P	27			YC053-YL999, YR301-YR328
2214B	22	X2			KN	35-4	49-62-12	D03599B	D13			D40854P	27			YN231-YN501
2214R	22	HF			KN	0-0	49-62-12	D03599B	C13			D10436	33			YC051-YC052
2214R	22	X2			KN	0-0	49-62-12	D03599B	C13			D40854P	28			YC053-YR328

WIRE LIST

D280A108

91-21-11

Section W5720

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5726	286A5726			LRU ECU TO APU FIREWALL AND E/E BAY (continued)											
2214Z				KN	0-0	49-62-12	D03599B			AE	D10436			AF	YC051-YC052
2214Z				KN	0-0	49-62-12	D03599B			AE	D40854P	S/R			YC053-YR328
2215B	22	HF		KP	48-6	49-62-12	D03599B	D12			D10436	19			YC051-YC052
2215B	22	X2		KP	35-3	49-62-12	D03599B	D12			D40854P	15			YC053-YL999, YR301-YR328
2215B	22	X2		KP	35-4	49-62-12	D03599B	D12			D40854P	15			YN231-YN501
2215R	22	HF		KP	0-0	49-62-12	D03599B	D11			D10436	35			YC051-YC052
2215R	22	X2		KP	0-0	49-62-12	D03599B	D11			D40854P	30			YC053-YR328
2215Z				KP	0-0	49-62-12	D03599B			AE	D10436			AF	YC051-YC052
2215Z				KP	0-0	49-62-12	D03599B			AE	D40854P	S/R			YC053-YR328
2216B	22	HF		KQ	48-6	49-62-12	D03599B	C12			D10436	20			YC051-YC052
2216B	22	X2		KQ	35-3	49-62-12	D03599B	C12			D40854P	31			YC053-YL999, YR301-YR328
2216B	22	X2		KQ	35-4	49-62-12	D03599B	C12			D40854P	31			YN231-YN501
2216R	22	HF		KQ	0-0	49-62-12	D03599B	C11			D10436	36			YC051-YC052
2216R	22	X2		KQ	0-0	49-62-12	D03599B	C11			D40854P	32			YC053-YR328
2216Z				KQ	0-0	49-62-12	D03599B			AE	D10436			AF	YC051-YC052
2216Z				KQ	0-0	49-62-12	D03599B			AE	D40854P	S/R			YC053-YR328
2217B	22	HF		KR	48-7	49-62-12	D03599A	A08			D10436	24			YC051-YC052
2217B	22	X2		KR	35-4	49-62-12	D03599A	A08			D40854P	35			YC053-YR328
2217R	22	HF		KR	0-0	49-62-12	D03599A	A07			D10436	3			YC051-YC052
2217R	22	X2		KR	0-0	49-62-12	D03599A	A07			D40854P	36			YC053-YR328
2217Z				KR	0-0	49-62-12	D03599A			AG	D10436			AH	YC051-YC052
2217Z				KR	0-0	49-62-12	D03599A			AG	D40854P	S/R			YC053-YR328
2218B	22	HF		KS	48-7	49-62-12	D03599A	D04			D10436	29			YC051-YC052
2218B	22	X2		KS	35-4	49-62-12	D03599A	D04			D40854P	37			YC053-YR328
2218R	22	HF		KS	0-0	49-62-12	D03599A	C04			D10436	28			YC051-YC052
2218R	22	X2		KS	0-0	49-62-12	D03599A	C04			D40854P	38			YC053-YR328
2218Z				KS	0-0	49-62-12	D03599A			AG	D10436			AH	YC051-YC052
2218Z				KS	0-0	49-62-12	D03599A			AG	D40854P	S/R			YC053-YR328
2219B	22	HF		KT	48-7	49-62-12	D03599A	B09			D10436	12			YC051-YC052
2219B	22	X2		KT	35-4	49-62-12	D03599A	B09			D40854P	22			YC053-YR328
2219R	22	HF		KT	0-0	49-62-12	D03599A	A09			D10436	26			YC051-YC052
2219R	22	X2		KT	0-0	49-62-12	D03599A	A09			D40854P	40			YC053-YR328
2219Z				KT	0-0	49-62-12	D03599A			AG	D10436			AH	YC051-YC052
2219Z				KT	0-0	49-62-12	D03599A			AG	D40854P	S/R			YC053-YR328
2220B	22	HF		KU	50-0	49-62-12	D03599B	B14			D10912	19			YC051-YC052
2220B	22	X2		KU	34-8	49-62-12	D03599B	B14			D40790P	28			YC053-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W5720

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5726	286A5726				LRU ECU TO APU FIREWALL AND E/E BAY (continued)										
2220B	22	X2	KU		34-9	49-62-12	D03599B	B14			D40790P	28			YN231-YN501
2220R	22	HF	KU		0-0	49-62-12	D03599B	B13			D10912	18			YC051-YC052
2220R	22	X2	KU		0-0	49-62-12	D03599B	B13			D40790P	29			YC053-YR328
2220Z			KU		0-0	49-62-12	D03599B	B15			D10912	7			YC051-YC052
2220Z			KU		0-0	49-62-12	D03599B	B15			D40790P	S/R			YC053-YR328
2221B	22	HF	KV		50-1	49-62-12	D03599A	D05			D10912	12			YC051-YC052
2221B	22	X2	KV		34-9	49-62-12	D03599A	D05			D40790P	30			YC053-YR328
2221R	22	HF	KV		0-0	49-62-12	D03599A	C05			D10912	26			YC051-YC052
2221R	22	X2	KV		0-0	49-62-12	D03599A	C05			D40790P	31			YC053-YR328
2221Z			KV		0-0	49-62-12	D03599A	B05			D10912	27			YC051-YC052
2221Z			KV		0-0	49-62-12	D03599A	B05			D40790P	S/R			YC053-YR328
2222B	22	HF	KW		50-1	49-62-12	D03599A	D13			D10912	24			YC051-YC052
2222B	22	X2	KW		34-9	49-62-12	D03599A	D13			D40790P	32			YC053-YR328
2222R	22	HF	KW		0-0	49-62-12	D03599A	D12			D10912	11			YC051-YC052
2222R	22	X2	KW		0-0	49-62-12	D03599A	D12			D40790P	33			YC053-YR328
2222Z			KW		0-0	49-62-12	D03599A	PERG	1A		D10912	25			YC051-YC052
2222Z			KW		0-0	49-62-12	D03599A	PERG	1A		D40790P	S/R			YC053-YR328
2223B	22	HF	KX		49-10	49-62-51	D03599A	B03			D10434	31			YC051-YC052
2223B	22	X2	KX		35-4	49-62-51	D03599A	B03			D40854P	44			YC053-YR328
2223R	22	HF	KX		0-0	49-62-51	D03599A	B02			D10434	30			YC051-YC052
2223R	22	X2	KX		0-0	49-62-51	D03599A	B02			D40854P	45			YC053-YR328
2223Z			KX		0-0	49-62-51	D03599A	DED			D10434	36			YC051-YC052
2223Z			KX		0-0	49-62-51	D03599A	DED			D40854P	S/R			YC053-YR328
2224B	22	HF	KY		49-10	49-62-51	D03599A	B06			D10434	33			YC051-YC052
2224B	22	X2	KY		35-4	49-62-51	D03599A	B06			D40854P	46			YC053-YR328
2224R	22	HF	KY		0-0	49-62-51	D03599A	B04			D10434	32			YC051-YC052
2224R	22	X2	KY		0-0	49-62-51	D03599A	B04			D40854P	47			YC053-YR328
2224Z			KY		0-0	49-62-51	D03599A	DED			D10434	35			YC051-YC052
2224Z			KY		0-0	49-62-51	D03599A	DED			D40854P	S/R			YC053-YR328
2226B	22	PB	LA		110-4	49-71-21	D03599A	A02			D40926P	B08			YC051-YC055
2226B	22	PB	LA		110-9	49-71-21	D03599A	A02			D40926P	B08			YC056-YL999, YR301-YR328
2226B	22	PB	LA		92-3	49-71-21	D03599A	A02			D40926P	B08			YN231-YN501
2226R	22	PB	LA		0-0	49-71-21	D03599A	A01			D40926P	A08			ALL
2227B	22	HF	LB		50-1	49-71-21	D03599A	D03			D10912	14			YC051-YC052
2227B	22	X2	LB		34-9	49-71-21	D03599A	D03			D40790P	38			YC053-YR328
2227R	22	HF	LB		0-0	49-71-21	D03599A	C03			D10912	13			YC051-YC052
2227R	22	X2	LB		0-0	49-71-21	D03599A	C03			D40790P	39			YC053-YR328
2227Z			LB		0-0	49-71-21	D03599A	PERG	1A		D10912	4			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W5720

Page 18

Nov 12/2012



WIRE LIST

91-21-11

Section W5720

Page 19

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5726	286A5726			LRU ECU TO APU FIREWALL AND E/E BAY (continued)											
3201B	22		HG	YA	48-7	49-52-31	D03599A	C14			D10436	10			YC051-YC052
3201B	22		X3	YA	35-4	49-52-31	D03599A	C14			D40854P	13			YC053-YR328
3201R	22		HG	YA	0-0	49-52-31	D03599A	D15			D10436	2			YC051-YC052
3201R	22		X3	YA	0-0	49-52-31	D03599A	D15			D40854P	14			YC053-YR328
3201Y	22		HG	YA	0-0	49-52-31	D03599A	C15			D10436	23			YC051-YC052
3201Y	22		X3	YA	0-0	49-52-31	D03599A	C15			D40854P	29			YC053-YR328
3201Z				YA	0-0	49-52-31	D03599A			AA	D10436			AB	YC051-YC052
3201Z				YA	0-0	49-52-31	D03599A			AA	D40854P	S/R			YC053-YR328
3202B	22		HG	YB	48-7	49-52-31	D03599A	B12			D10436	16			YC051-YC052
3202B	22		X3	YB	35-4	49-52-31	D03599A	B12			D40854P	20			YC053-YR328
3202R	22		HG	YB	0-0	49-52-31	D03599A	B13			D10436	31			YC051-YC052
3202R	22		X3	YB	0-0	49-52-31	D03599A	B13			D40854P	21			YC053-YR328
3202Y	22		HG	YB	0-0	49-52-31	D03599A	A13			D10436	6			YC051-YC052
3202Y	22		X3	YB	0-0	49-52-31	D03599A	A13			D40854P	39			YC053-YR328
3202Z				YB	0-0	49-52-31	D03599A			AC	D10436			AD	YC051-YC052
3202Z				YB	0-0	49-52-31	D03599A			AC	D40854P	S/R			YC053-YR328
3203B	22		HG	YC	48-7	49-62-12	D03599A	A06			D10436	11			YC051-YC052
3203B	22		X3	YC	35-4	49-62-12	D03599A	A06			D40854P	41			YC053-YR328
3203R	22		HG	YC	0-0	49-62-12	D03599A	A05			D10436	4			YC051-YC052
3203R	22		X3	YC	0-0	49-62-12	D03599A	A05			D40854P	42			YC053-YR328
3203Y	22		HG	YC	0-0	49-62-12	D03599A	A04			D10436	25			YC051-YC052
3203Y	22		X3	YC	0-0	49-62-12	D03599A	A04			D40854P	23			YC053-YR328
3203Z				YC	0-0	49-62-12	D03599A			AG	D10436			AH	YC051-YC052
3203Z				YC	0-0	49-62-12	D03599A			AG	D40854P	S/R			YC053-YR328
3204B	16		VH	YD	132-8	24-21-31	D40912P	J			D11118	10			YC051-YC052
3204B	16		VH	YD	114-11	24-21-31	D40912P	J			D40876P	1			YC053-YC055
3204B	16		VH	YD	115-4	24-21-31	D40912P	J			D40876P	1			YC056-YL999, YR301-YR328
3204B	16		VH	YD	96-7	24-21-31	D40912P	J			D40876P	1			YN231-YN501
3204R	16		VH	YD	0-0	24-21-31	D40912P	H			D11118	25			YC051-YC052
3204R	16		VH	YD	0-0	24-21-31	D40912P	H			D40876P	2			YC053-YR328
3204Y	16		VH	YD	0-0	24-21-31	D40912P	K			D11118	24			YC051-YC052
3204Y	16		VH	YD	0-0	24-21-31	D40912P	K			D40876P	3			YC053-YR328
3204Z				YD	0-0	24-21-31	D40912P	B10			D11118	11			YC051-YC052
3204Z				YD	0-0	24-21-31	D40912P	B10			D40876P	4			YC053-YR328
3205B	20		PC	YE	4-0	24-22-31	D11436	23			D40910P	B01			ALL
3205R	20		PC	YE	0-0	24-22-31	D11436	20			D40910P	A01			ALL
3205Y	20		PC	YE	0-0	24-22-31	D11436	21			D40910P	A02			ALL
4101B	20		PD	N6	2-11	24-21-31	D11436	4			D40942P	B03			ALL

WIRE LIST

D280A108

91-21-11

Section W5720

Page 20

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From				To						
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice
W5726	286A5726			LRU ECU TO APU FIREWALL AND E/E BAY (continued)											
4101G	20	PD	N6		0-0	24-21-31	D11436		5		D40942P	B04			ALL
4101R	20	PD	N6		0-0	24-21-31	D11436		15		D40942P	A03			ALL
4101Y	20	PD	N6		0-0	24-21-31	D11436		14		D40942P	A04			ALL
4102B	20	HD	P6		4-7	24-21-31	D40910P		G		D11438	6			YC051-YC052
4102B	20	PD	P6		4-7	24-21-31	D40910P		G		D11438	6			YC053-YR328
4102G	20	HD	P6		0-0	24-21-31	D40910P		J		GD00276	ST..	E		YC051-YC052
4102G	20	PD	P6		0-0	24-21-31	D40910P		J		GD00276	ST..	E		YC053-YR328
4102R	20	HD	P6		0-0	24-21-31	D40910P		F		D11438	1			YC051-YC052
4102R	20	PD	P6		0-0	24-21-31	D40910P		F		D11438	1			YC053-YR328
4102Y	20	HD	P6		0-0	24-21-31	D40910P		H		D11438	5			YC051-YC052
4102Y	20	PD	P6		0-0	24-21-31	D40910P		H		D11438	5			YC053-YR328
4103B	20	HS	Q6		129-1	24-24-31	D11118		23		D40910P	B02			YC051-YC052
4103B	20	X4	Q6		111-2	24-24-31	D40790P		7		D40910P	B02			YC053-YC055
4103B	20	X4	Q6		111-7	24-24-31	D40790P		7		D40910P	B02			YC056-YL999, YR301-YR328
4103B	20	X4	Q6		92-10	24-24-31	D40790P		7		D40910P	B02			YN231-YN501
4103G	20	HS	Q6		0-0	24-24-31	D11118		4		D40910P	A04			YC051-YC052
4103G	20	X4	Q6		0-0	24-24-31	D40790P		19		D40910P	A04			YC053-YR328
4103R	20	HS	Q6		0-0	24-24-31	D11118		3		D40910P	A03			YC051-YC052
4103R	20	X4	Q6		0-0	24-24-31	D40790P		8		D40910P	A03			YC053-YR328
4103Y	20	HS	Q6		0-0	24-24-31	D11118		22		D40910P	B03			YC051-YC052
4103Y	20	X4	Q6		0-0	24-24-31	D40790P		18		D40910P	B03			YC053-YR328
4103Z			Q6		0-0	24-24-31	D11118	DED			D40910P	PERG	1F		YC051-YC052
4103Z			Q6		0-0	24-24-31	D40790P	S/R			D40910P	PERG	1F		YC053-YR328
4104B	22	PD	R6		4-0	24-24-31	D11436		7		D40910P	A05			ALL
4104G	22	PD	R6		0-0	24-24-31	D11436		6		D40910P	A06			ALL
4104R	22	PD	R6		0-0	24-24-31	D11436		17		D40910P	B04			ALL
4104Y	22	PD	R6		0-0	24-24-31	D11436		18		D40910P	B05			ALL
4501G	22	XU	A8		0-7	49-71-21	D03599A		D06		SM00009		9		ALL
4501W	22	XU	A8		0-0	49-71-21	D03599A		C06		SM00010		9		ALL
4502G	20	DU	B8		50-1	49-71-21	SM00009		9		D10912	5			YC051-YC052
4502G	20	DU	B8		34-9	49-71-21	SM00009		9		D40790P	41			YC053-YR328
4502W	20	DU	B8		0-0	49-71-21	SM00010		9		D10912	1			YC051-YC052
4502W	20	DU	B8		0-0	49-71-21	SM00010		9		D40790P	42			YC053-YR328
4502Z			B8		0-0	49-71-21	D03599A	PERG	1A		D10912	6			YC051-YC052
4502Z			B8		0-0	49-71-21	D03599A	PERG	1A		D40790P	S/R			YC053-YR328
4503G	22	XU	C8		0-7	49-71-21	D03599A		D07		SM00011		9		ALL
4503W	22	XU	C8		0-0	49-71-21	D03599A		C07		SM00012		9		ALL
4504G	20	DU	D8		50-1	49-71-21	SM00011		9		D10912	16			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W5720

Page 21

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W5726	286A5726	LRU ECU TO APU FIREWALL AND E/E BAY (continued)													
4504G	20	DU	D8	34-9	49-71-21	SM00011		9	D40790P	44			YC053-YR328		
4504W	20	DU	D8	0-0	49-71-21	SM00012		9	D10912	15			YC051-YC052		
4504W	20	DU	D8	0-0	49-71-21	SM00012		9	D40790P	45			YC053-YR328		
4504Z			D8	0-0	49-71-21	D03599A	PERG	1A	D10912	17			YC051-YC052		
4504Z			D8	0-0	49-71-21	D03599A	PERG	1A	D40790P	S/R			YC053-YR328		
5501	24	B6		112-4	21-51-11	D40908P	A04		D03599B	B12			YC051-YC055, YD158-YL954		
5501	24	B6		112-6	21-51-11	D40908P	A04		D03599B	B12			YC056-YD157, YL955-YL999, YR301-YR328		
5501	24	B6		94-2	21-51-11	D40908P	A04		D03599B	B12			YN231-YN501		
6001R	20	PH		0-10	26-11-31	D40928P	A02		SM00017		9		ALL		
6014	24	PK		8-5	31-35-05	D40904P	A07		D40908P	B07			YL963-YL999, YN236-YR328		
6015	24	PK		8-5	31-35-05	D40904P	A08		D40908P	B08			YL963-YL999, YN236-YR328		
FRAA				0-0	49-52-31	D03599A	D14		D03599A			AA	YC051-YC052		
FRAA				0-0	49-52-31	D03599A	PERG	1A	D03599A			AA	YC053-YR328		
FRAB				0-0	49-52-31	D10436		7	D10436			AB	YC051-YC052		
FRAC				0-0	49-52-31	D03599A	B11		D03599A			AC	YC051-YC052		
FRAC				0-0	49-52-31	D03599A	PERG	1A	D03599A			AC	YC053-YR328		
FRAD				0-0	49-52-31	D10436		14	D10436			AD	YC051-YC052		
FRAE				0-0	49-62-12	D03599B	PERG	1A	D03599B			AE	ALL		
FRAF				0-0	49-62-12	D10436		17	D10436			AF	YC051-YC052		
FRAG				0-0	49-62-12	D03599A	B08		D03599A			AG	YC051-YC052		
FRAG				0-0	49-62-12	D03599A	PERG	1A	D03599A			AG	YC053-YR328		
FRAH				0-0	49-62-12	D10436		13	D10436			AH	YC051-YC052		
YAAA				0-0	49-41-11	D10434	S/R		GD04815	ST..	E	*2	YC051-YC052		
YAAB				0-0	49-52-31	D10434	S/R		GD00098	ST..	1		YC051-YC052		
YAAC				0-0	49-41-11	D11118	S/R		GD04815	ST..	E	*2	YC051-YC052		
YAAD				0-0	33-35-11	D44584P	S/R		GD00078	ST..	1		YC051-YC052		
YAAE				0-0	33-35-11	D44584P	S/R		GD04815	ST..	E	*1	YC051-YC052		
YAAF				0-0	33-35-11	S00087	DED		GD04815	ST..	E	*1	YC051-YC052		
YAAG				0-0	33-35-11	D40060J	S/R		GD04815	ST..	E	*1	YC051-YC052		
YAAH				0-0	26-21-11	GD04813	ST..	E	GD00098	ST..	1		YC051-YC052		
YAAJ				0-0	26-21-11	GD04813	ST..	E	GD04804	ST..	E	*	YC051-YC052		
YAAK				0-0	26-21-11	GD04813	ST..	E	GD04804	ST..	E	*	YC051-YC052		
YAAL				0-0	26-21-11	GD04813	ST..	E	GD00098	ST..	1		YC051-YC052		
YAAM				0-0	26-11-31	GD04813	ST..	E	M01925	DED			YC051-YC052		

WIRE LIST

D280A108

91-21-11

Section W5720

Page 22

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5726	286A5726			LRU ECU TO APU FIREWALL AND E/E BAY (continued)											
YAAN					0-0	26-11-31	D40060J		S/R		M01925	DED			YC051-YC052
YAAP					0-0	26-11-31	D40060J		S/R		GD04815	ST..	E	*3	YC051-YC052
YAAQ					0-0	49-62-12	D10436		S/R		GD00098	ST..	1		YC051-YC052
YAAR					0-0	49-62-11	GD04807		ST..	E	GD00048	ST..	1		YC051-YC052
YAAS					0-0	49-62-11	GD04807		ST..	E	GD04815	ST..	E	*2	YC051-YC052
YAAT					0-0	49-62-11	GD04805		ST..	E	GD04815	ST..	E	*2	YC051-YC052
YAAU					0-0	49-52-31	D10912		S/R		GD04815	ST..	E	*3	YC051-YC052
YAAV					0-0	49-52-31	D10436		S/R		GD04815	ST..	E	*3	YC051-YC052
W5728	286A5728			DISC AL0675ATO E2-2 (WITH E6)											
0001	20		HA		49-4	33-32-11	D43024P		A04		D46026J		9		YC051-YC055
0001	20		HA		49-8	33-32-11	D43024P		A04		D46026J		9		YC056-YL999, YR301-YR328
0001	20		HA		39-7	33-32-11	D43024P		A04		D46026J		9		YN231-YN501
0002	20		HA		49-4	33-32-11	D43024P		B04		D46026J		5		YC051-YC055
0002	20		HA		49-8	33-32-11	D43024P		B04		D46026J		5		YC056-YL999, YR301-YR328
0002	20		HA		39-7	33-32-11	D43024P		B04		D46026J		5		YN231-YN501
0501	20		PA		58-4	49-62-11	SP00256			S	D46026J		1		YC051-YL999, YR301-YR328
0501	20		PA		48-6	49-62-11	SP00256			S	D46026J		1		YN231-YN501
0502	20		PA		58-4	49-62-11	SP00254			S	D46026J		2		YC051-YL999, YR301-YR328
0502	20		PA		48-6	49-62-11	SP00254			S	D46026J		2		YN231-YN501
0503	20		PA		58-4	49-62-11	SP00258			S	D46026J		3		YC051-YL999, YR301-YR328
0503	20		PA		48-6	49-62-11	SP00258			S	D46026J		3		YN231-YN501
0504	20		PA		58-4	49-62-11	SP00252			S	D46026J		4		YC051-YL999, YR301-YR328
0504	20		PA		48-6	49-62-11	SP00252			S	D46026J		4		YN231-YN501
0512	20		PA		16-7	32-35-11	D46026J		6		GD05108	DC..	1		ALL
0513	20		PA		49-4	32-35-11	D43024P		A03		D46026J		8		YC051-YC055
0513	20		PA		49-8	32-35-11	D43024P		A03		D46026J		8		YC056-YL999, YR301-YR328
0513	20		PA		39-7	32-35-11	D43024P		A03		D46026J		8		YN231-YN501
0591	22		PA		49-4	32-41-11	D43024P		B03		D46026J		10		YC051-YC055
0591	22		PA		49-8	32-41-11	D43024P		B03		D46026J		10		YC056-YL999, YR301-YR328
0591	22		PA		39-7	32-41-11	D43024P		B03		D46026J		10		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W5720

Page 23

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W5728		286A5728			DISC AL0675ATO E2-2 (WITH E6) (continued)											
0592		22		PA		16-7	32-41-11	D46026J		11		GD05108	DC..	1		ALL

For training purposes only!

WIRE LIST
D280A108

91-21-11
Section W5720
Page 24 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I	W5837	286A5837			LOC ANT LEFT - STA 178 TO R315 - LOC ANTENNA SWITCH RELAY-1										
I	001CO			AA	0-0	34-31-11	D03321		= C1		D02117		= C1		ALL
I	001CX		0F	AA	17-5	34-31-11	D03321		= A1		D02117		= A1		ALL
I	W5839	286A5839			LOC ANT RIGHT - R316 - LOC ANTENNA SWITCH RELAY-2										
I	001CO			AA	0-0	34-31-21	D03323		= C1		D02125		= C1		ALL
I	001CX		0F	AA	18-3	34-31-21	D03323		= A1		D02125		= A1		ALL

WIRE LIST

D280A108

91-21-11

Section W5830

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6024	286A6024				P19 (EXTERNAL POWER RECP PANEL) TO P6 DISC											
0202	22		PA		11-6	23-43-11		D44252P		8		TB0608Z	A005	1A		YD158-YL954, YN231-YN235
0202	22		PA		11-0	23-43-11		D40664		8		TB0608Z	A005	1A		YL955-YL999, YN236-YR328
0203	22		PA		10-1	23-42-11		D40654P		7		TB0608Z	A005	1A		YD158-YR328
0301	22		PA		8-3	33-29-11		D40654P		12		D00048	E	E		YC051-YL954, YN231-YN235
0301	22		PA		8-1	33-29-11		D40654P		12		D00048	E	E		YL955-YL999, YN236, YN501-YR312
0301	22		PA		8-7	33-29-11		D40654P		12		D00048	E	E		YN237-YN260, YR313-YR328
0501	18		HA		1-9	33-32-11		L00171	= G	GW		GD00396	AC..	E		ALL
0502	18		HA		15-2	33-32-11		D44252P		11	18	L00171	= P	G7		YC051-YL954, YN231-YN235
0502	18		HA		14-8	33-32-11		D40664		11	18	L00171	= P	G7		YL955-YL999, YN236-YR328
0503	22		PA		2-9	24-41-11		D44252P		3		GD00612	AC..	E		YC051-YL954, YN231-YN235
0503	22		PA		2-3	24-41-11		D40664		27		GD00612	AC..	E		YL955-YL999, YN236-YR328
0504	22		PA		8-0	24-41-11		D44252P		4		D40654P		4		YC051-YL954, YN231-YN235
0504	22		PA		7-6	24-41-11		D40664		4		D40654P		4		YL955-YL999, YN236-YR328
0505	22		PA		8-0	23-43-11		D44252P		5		D40654P		5		YC051-YL954, YN231-YN235
0505	22		PA		7-6	23-43-11		D40664		22		D40654P		5		YL955-YL999, YN236-YR328
0506	22		PA		8-0	23-43-11		D44252P		6		D40654P		6		YC051-YL954, YN231-YN235
0506	22		PA		7-6	23-43-11		D40664		19		D40654P		6		YL955-YL999, YN236-YR328
0507	22		PA		8-0	23-42-11		D44252P		7		D40654P		7		YC051-YD157
0508	22		PA		11-6	23-42-11		D44252P		8		TB0606X	A003	1A		YC051-YD157
0509	20		HA		8-0	33-32-11		D44252P		9		D40654P		9		YC051-YL954, YN231-YN235
0509	20		HA		7-6	33-32-11		D40664		18		D40654P		9		YL955-YL999, YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W6020

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6024	286A6024			P19 (EXTERNAL POWER RECP PANEL) TO P6 DISC (continued)											
0510	20		HA		8-0	33-32-11	D44252P	10			D40654P	10			YC051-YL954, YN231-YN235
0510	20		HA		7-6	33-32-11	D40664	20			D40654P	10			YL955-YL999, YN236-YR328
0512	22		PA		18-8	23-43-11	TB0606X	B003	1A		M00053	=P	C		ALL
0513	22		PA		3-4	23-43-11	M00053	=G	C		GD00360	DC..	E		ALL
0516	22		PA		9-1	32-44-11	D44252P	13			GD00034	DC..	1		YC051-YD157
0517	24		PK		8-0	32-44-11	D44252P	12			D40654P	3			YC051-YD157
W6026	286A6026			P92 TO P19(EXTERNAL PWR RECP PNL)											
0001	*1		QY		20-9	24-41-11	D00048	A	H1		TB5006	A	H1		YC051-YL954, YN231-YN235
0001	*1		QY		21-1	24-41-11	D00048	A	H1		TB5006	A	H1		YL955-YL999, YN236, YN501-YR312
0001	*1		QY		22-2	24-41-11	D00048	A	H1		TB5006	A	H1		YR313-YR328
0002	*1		QY		21-2	24-41-11	D00048	B	H1		TB5006	B	H1		YC051-YL954, YN231-YN235
0002	*1		QY		21-1	24-41-11	D00048	B	H1		TB5006	B	H1		YL955-YL999, YN236, YN501-YR328
0003	*1		QY		21-4	24-41-11	D00048	C	H1		TB5006	C	H1		YC051-YL954, YN231-YN235
0003	*1		QY		21-2	24-41-11	D00048	C	H1		TB5006	C	H1		YL955-YL999, YN236, YN501-YR328
0004	04		CQ		1-4	24-41-11	D00048	N	H		GD00038	AC..	H7		YC051-YL954, YN231-YN235
0004	04		CQ		2-4	24-41-11	D00048	N	H		GD00038	AC..	H7		YL955-YL999, YN236, YN501-YR312
0004	04		CQ		1-6	24-41-11	D00048	N	H		GD00038	AC..	H7		YR313-YR328
W6028	286A6028			MAIN WHEEL WELL TO E/E BAY VIA CROWN											
2010B	22		PB	GJ	102-0	27-53-21	D40180P	B07			D43104J	8			YC051-YC055
2010B	22		PB	GJ	101-8	27-53-21	D40180P	B07			D43104J	8			YC056-YD158
2010B	22		PB	GJ	97-2	27-53-21	D40180P	B07			D43104J	8			YD160-YL999
2010B	22		PB	GJ	87-1	27-53-21	D40180P	B07			D43104J	8			YN231-YN260
2010B	22		PB	GJ	87-7	27-53-21	D40180P	B07			D43104J	8			YN501
2010B	22		PB	GJ	97-8	27-53-21	D40180P	B07			D43104J	8			YR301-YR328
2010R	22		PB	GJ	0-0	27-53-21	D40180P	A07			D43104J	7			ALL
2206B	22		X2	KF	102-0	27-52-11	D40180P	B08			D43104J	2			YC051-YC055
2206B	22		X2	KF	101-8	27-52-11	D40180P	B08			D43104J	2			YC056-YD158

WIRE LIST

D280A108

91-21-11

Section W6020

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W6028	286A6028				MAIN WHEEL WELL TO E/E BAY VIA CROWN (continued)												
2206B	22	X2	KF		97-2	27-52-11	D40180P		B08		D43104J	2			YD160-YL999		
2206B	22	X2	KF		87-1	27-52-11	D40180P		B08		D43104J	2			YN231-YN260		
2206B	22	X2	KF		87-7	27-52-11	D40180P		B08		D43104J	2			YN501		
2206B	22	X2	KF		97-8	27-52-11	D40180P		B08		D43104J	2			YR301-YR328		
2206R	22	X2	KF		0-0	27-52-11	D40180P		A08		D43104J	1			ALL		
2206Z			KF		0-0	27-52-11	D40180P		A09		D43104J	3			ALL		
2207B	20	X2	KG		102-0	27-52-11	D40180P		B10		D43104J	5			YC051-YC055		
2207B	20	X2	KG		101-8	27-52-11	D40180P		B10		D43104J	5			YC056-YD158		
2207B	20	X2	KG		97-2	27-52-11	D40180P		B10		D43104J	5			YD160-YL999		
2207B	20	X2	KG		87-1	27-52-11	D40180P		B10		D43104J	5			YN231-YN260		
2207B	20	X2	KG		87-7	27-52-11	D40180P		B10		D43104J	5			YN501		
2207B	20	X2	KG		97-8	27-52-11	D40180P		B10		D43104J	5			YR301-YR328		
2207R	20	X2	KG		0-0	27-52-11	D40180P		A10		D43104J	4			ALL		
2207Z			KG		0-0	27-52-11	D40180P		B09		D43104J	6			ALL		
3006B	22	PC	WF		102-0	27-53-21	D40180P		B02		D43104J	10			YC051-YC055		
3006B	22	PC	WF		101-8	27-53-21	D40180P		B02		D43104J	10			YC056-YD158		
3006B	22	PC	WF		97-2	27-53-21	D40180P		B02		D43104J	10			YD160-YL999		
3006B	22	PC	WF		87-1	27-53-21	D40180P		B02		D43104J	10			YN231-YN260		
3006B	22	PC	WF		87-7	27-53-21	D40180P		B02		D43104J	10			YN501		
3006B	22	PC	WF		97-8	27-53-21	D40180P		B02		D43104J	10			YR301-YR328		
3006R	22	PC	WF		0-0	27-53-21	D40180P		B01		D43104J	9			ALL		
3006Y	22	PC	WF		0-0	27-53-21	D40180P		B03		D43104J	11			ALL		
3007B	22	PC	WG		102-0	27-53-21	D40180P		B05		D43104J	13			YC051-YC055		
3007B	22	PC	WG		101-8	27-53-21	D40180P		B05		D43104J	13			YC056-YD158		
3007B	22	PC	WG		97-2	27-53-21	D40180P		B05		D43104J	13			YD160-YL999		
3007B	22	PC	WG		87-1	27-53-21	D40180P		B05		D43104J	13			YN231-YN260		
3007B	22	PC	WG		87-7	27-53-21	D40180P		B05		D43104J	13			YN501		
3007B	22	PC	WG		97-8	27-53-21	D40180P		B05		D43104J	13			YR301-YR328		
3007R	22	PC	WG		0-0	27-53-21	D40180P		B04		D43104J	12			ALL		
3007Y	22	PC	WG		0-0	27-53-21	D40180P		B06		D43104J	14			ALL		
3008B	22	PC	WH		102-0	27-53-21	D40180P		A02		D43104J	17			YC051-YC055		
3008B	22	PC	WH		101-8	27-53-21	D40180P		A02		D43104J	17			YC056-YD158		
3008B	22	PC	WH		97-2	27-53-21	D40180P		A02		D43104J	17			YD160-YL999		
3008B	22	PC	WH		87-1	27-53-21	D40180P		A02		D43104J	17			YN231-YN260		
3008B	22	PC	WH		87-7	27-53-21	D40180P		A02		D43104J	17			YN501		
3008B	22	PC	WH		97-8	27-53-21	D40180P		A02		D43104J	17			YR301-YR328		
3008R	22	PC	WH		0-0	27-53-21	D40180P		A01		D43104J	16			ALL		
3008Y	22	PC	WH		0-0	27-53-21	D40180P		A03		D43104J	18			ALL		
3009B	22	PC	WI		102-0	27-53-21	D40180P		A05		D43104J	21			YC051-YC055		

WIRE LIST

D280A108

91-21-11

Section W6020

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity

W6028		286A6028		MAIN WHEEL WELL TO E/E BAY VIA CROWN (continued)											
3009B	22	PC	WI		101-8	27-53-21	D40180P	A05			D43104J	21			YC056-YD158
3009B	22	PC	WI		97-2	27-53-21	D40180P	A05			D43104J	21			YD160-YL999
3009B	22	PC	WI		87-1	27-53-21	D40180P	A05			D43104J	21			YN231-YN260
3009B	22	PC	WI		87-7	27-53-21	D40180P	A05			D43104J	21			YN501
3009B	22	PC	WI		97-8	27-53-21	D40180P	A05			D43104J	21			YR301-YR328
3009R	22	PC	WI		0-0	27-53-21	D40180P	A04			D43104J	20			ALL
3009Y	22	PC	WI		0-0	27-53-21	D40180P	A06			D43104J	22			ALL
6001	20	CQ			4-2	28-21-11	SP00458		S		D43104J	25			ALL

WIRE LIST

D280A108

91-21-11

Section W6020

Page 4 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6032	286A6032				DISC AB0500DR TO E4-2.										
0030	20		PA		31-0	31-31-15	D40416J		8		D43028P	A06			YC065-YL999, YR301-YR328
0030	20		PA		21-2	31-31-15	D40416J		8		D43028P	A06			YN231-YN501
0503	20		PA		31-0	27-23-11	D43028P		A02		D40402J	3			YC051-YC055
0503	20		PA		31-3	27-23-11	D43028P		A02		D40402J	3			YC056-YL999, YR301-YR328
0503	20		PA		21-3	27-23-11	D43028P		A02		D40402J	3			YN231-YN501
0504	20		PA		31-0	27-23-11	D43028P		B02		D40402J	4			YC051-YC055
0504	20		PA		31-3	27-23-11	D43028P		B02		D40402J	4			YC056-YL999, YR301-YR328
0504	20		PA		21-3	27-23-11	D43028P		B02		D40402J	4			YN231-YN501
0511	22		PA		31-0	27-54-11	D43028P		B05		D40402J	23			YC051-YC055
0511	22		PA		31-3	27-54-11	D43028P		B05		D40402J	23			YC056-YL999, YR301-YR328
0511	22		PA		21-6	27-54-11	D43028P		B05		D40402J	23			YN231-YN501
0512	20		PA		30-10	27-61-11	D43028P		B07		D40416J	6			YC051-YC055
0512	20		PA		31-0	27-61-11	D43028P		B07		D40416J	6			YC056-YL999, YR301-YR328
0512	20		PA		20-11	27-61-11	D43028P		B07		D40416J	6			YN231-YN501
0513	20		PA		30-10	27-61-11	D43028P		A08		D40416J	3			YC051-YC055
0513	20		PA		31-0	27-61-11	D43028P		A08		D40416J	3			YC056-YL999, YR301-YR328
0513	20		PA		20-11	27-61-11	D43028P		A08		D40416J	3			YN231-YN501
0514	20		PA		30-10	27-23-11	D43028P		B08		D40416J	1			YC051-YC055
0514	20		PA		31-0	27-23-11	D43028P		B08		D40416J	1			YC056-YL999, YR301-YR328
0514	20		PA		20-11	27-23-11	D43028P		B08		D40416J	1			YN231-YN501
0515	20		PA		30-10	27-23-11	D43028P		A09		D40416J	2			YC051-YC055
0515	20		PA		31-0	27-23-11	D43028P		A09		D40416J	2			YC056-YL999, YR301-YR328
0515	20		PA		20-11	27-23-11	D43028P		A09		D40416J	2			YN231-YN501
0521	22		PA		31-0	27-54-11	D43028P		B09		D40402J	22			YC051-YC055
0521	22		PA		31-3	27-54-11	D43028P		B09		D40402J	22			YC056-YL999, YR301-YR328
0521	22		PA		21-6	27-54-11	D43028P		B09		D40402J	22			YN231-YN501
0523	20		PA		31-0	29-23-11	D43028P		A10		D40402J	24			YC051-YC055
0523	20		PA		31-3	29-23-11	D43028P		A10		D40402J	24			YC056-YL999, YR301-YR328
0523	20		PA		21-3	29-23-11	D43028P		A10		D40402J	24			YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W6030

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W6032	286A6032				DISC AB0500DR TO E4-2. (continued)											
0524	20		PA		31-0	29-23-11		D43028P	B10			D40402J	15			YC051-YC055
0524	20		PA		31-3	29-23-11		D43028P	B10			D40402J	15			YC056-YL999, YR301-YR328
0524	20		PA		21-6	29-23-11		D43028P	B10			D40402J	15			YN231-YN501
0542	20		PA		31-0	27-61-11		D43028P	B06			D40402J	17			YC051-YC055
0542	20		PA		31-3	27-61-11		D43028P	B06			D40402J	17			YC056-YL999, YR301-YR328
0542	20		PA		21-3	27-61-11		D43028P	B06			D40402J	17			YN231-YN501
0543	20		PA		31-0	27-61-11		D43028P	A07			D40402J	18			YC051-YC055
0543	20		PA		31-3	27-61-11		D43028P	A07			D40402J	18			YC056-YL999, YR301-YR328
0543	20		PA		21-3	27-61-11		D43028P	A07			D40402J	18			YN231-YN501
W6034	286A6034				DISC AB0500DR TO E3-2											
0001	20		PA		30-9	33-25-11		D43030P	B04			D40404J	11			YC051-YC055
0001	20		PA		31-1	33-25-11		D43030P	B04			D40404J	11			YC056-YL999, YR301-YR328
0001	20		PA		21-3	33-25-11		D43030P	B04			D40404J	11			YN231-YN501
0030	22		PA		31-1	31-31-15		D40404J	3			D43030P	A02			YC065-YL999, YR301-YR328
0030	22		PA		21-3	31-31-15		D40404J	3			D43030P	A02			YN231-YN501
0501	20		CQ		30-9	27-31-11		D43030P	B02			D40404J	7			YC051-YC055
0501	20		CQ		31-1	27-31-11		D43030P	B02			D40404J	7			YC056-YL999, YR301-YR328
0501	20		CQ		21-3	27-31-11		D43030P	B02			D40404J	7			YN231-YN501
0550	22		PA		30-9	22-23-12		D43030P	A04			D40404J	5			YC051-YC055
0550	22		PA		31-1	22-23-12		D43030P	A04			D40404J	5			YC056-YL999, YR301-YR328
0550	22		PA		21-3	22-23-12		D43030P	A04			D40404J	5			YN231-YN501
0561	22		CQ		30-9	32-64-21		D43030P	B10			D40404J	14			YC051-YC055
0561	22		CQ		31-1	32-64-21		D43030P	B10			D40404J	14			YC056-YL999, YR301-YR328
0561	22		CQ		21-3	32-64-21		D43030P	B10			D40404J	14			YN231-YN501
0562	22		CQ		30-9	32-64-21		D43030P	A01			D40404J	26			YC051-YC055
0562	22		CQ		31-1	32-64-21		D43030P	A01			D40404J	26			YC056-YL999, YR301-YR328
0562	22		CQ		21-3	32-64-21		D43030P	A01			D40404J	26			YN231-YN501
2201B	22		PB	KA	30-9	31-53-11		D43030P	B09			D40404J	12			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W6030

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6034	286A6034				DISC AB0500DR TO E3-2 (continued)										
2201B	22	PB	KA		31-1	31-53-11	D43030P	B09			D40404J	12			YC056-YL999, YR301-YR328
2201B	22	PB	KA		21-3	31-53-11	D43030P	B09			D40404J	12			YN231-YN501
2201R	22	PB	KA		0-0	31-53-11	D43030P	A09			D40404J	4			ALL
5501	24	PK			30-9	21-51-14	D43030P	A05			D40404J	9			YC051-YC055
5501	24	PK			31-1	21-51-14	D43030P	A05			D40404J	9			YC056-YL999, YR301-YR328
5501	24	PK			21-3	21-51-14	D43030P	A05			D40404J	9			YN231-YN501

WIRE LIST
D280A108

91-21-11
Section W6030
Page 3 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type
W6102	286A6102			CABIN PRESSURE OUTFLOW VALVE TO E/E BAY (LA2)										
1001	20	X1	AA	103-6	21-31-22	D40240P	A02			D10732	L			YC051-YC055
1001	20	X1	AA	104-4	21-31-22	D40240P	A02			D10732	L			YC056-YL999, YR301-YR319
1001	20	X1	AA	85-0	21-31-22	D40240P	A02			D10732	L			YN231-YN501
1001	20	X1	AA	107-2	21-31-22	D40240P	A02			D10732	L			YR320-YR328
1001Z			AA	0-0	21-31-22	D40240P	PERG	1F		GD03738	ST..	1		ALL
2001B	24	Y2	GA	103-6	21-31-22	D40240P	A04			D10732	P			YC051-YC055
2001B	24	Y2	GA	104-4	21-31-22	D40240P	A04			D10732	P			YC056-YL999, YR301-YR319
2001B	24	Y2	GA	85-0	21-31-22	D40240P	A04			D10732	P			YN231-YN501
2001B	24	Y2	GA	107-2	21-31-22	D40240P	A04			D10732	P			YR320-YR328
2001R	24	Y2	GA	0-0	21-31-22	D40240P	A03			D10732	R			ALL
2001Z			GA	0-0	21-31-22	D40240P	PERG	1F		GD03738	ST..	1		ALL
2002B	24	Y2	GB	103-6	21-31-22	D40240P	A06			D10732	M			YC051-YC055
2002B	24	Y2	GB	104-4	21-31-22	D40240P	A06			D10732	M			YC056-YL999, YR301-YR319
2002B	24	Y2	GB	85-0	21-31-22	D40240P	A06			D10732	M			YN231-YN501
2002B	24	Y2	GB	107-2	21-31-22	D40240P	A06			D10732	M			YR320-YR328
2002R	24	Y2	GB	0-0	21-31-22	D40240P	A05			D10732	N			ALL
2002Z			GB	0-0	21-31-22	D40240P	PERG	1F		GD03738	ST..	1		ALL
2003B	24	PL	GC	2-10	21-31-22	D10732	E			D10728	D			YC051-YC055
2003B	24	PL	GC	4-6	21-31-22	D10732	E			D10728	D			YC056-YR328
2003R	24	PL	GC	0-0	21-31-22	D10732	F			D10728	E			ALL
2004B	22	X2	GD	106-11	21-31-11	D40242P	A02			D10730	B			YC051-YC055
2004B	22	X2	GD	107-5	21-31-11	D40242P	A02			D10730	B			YC056-YL999, YR301-YR319
2004B	22	X2	GD	88-1	21-31-11	D40242P	A02			D10730	B			YN231-YN501
2004B	22	X2	GD	110-3	21-31-11	D40242P	A02			D10730	B			YR320-YR328
2004R	22	X2	GD	0-0	21-31-11	D40242P	A01			D10730	A			ALL
2004Z			GD	0-0	21-31-11	D40242P	PERG	1F		GD03738	ST..	1		ALL
3001B	24	PM	WA	2-10	21-31-22	D10732	B			D10728	B			YC051-YC055
3001B	24	PM	WA	4-6	21-31-22	D10732	B			D10728	B			YC056-YR328
3001R	24	PM	WA	0-0	21-31-22	D10732	C			D10728	C			ALL
3001Y	24	PM	WA	0-0	21-31-22	D10732	A			D10728	A			ALL
3002B	24	Y3	WB	105-10	21-31-11	D40242P	A05			D10728	H			YC051-YC055
3002B	24	Y3	WB	106-7	21-31-11	D40242P	A05			D10728	H			YC056-YL999, YR301-YR319
3002B	24	Y3	WB	87-3	21-31-11	D40242P	A05			D10728	H			YN231-YN501
3002B	24	Y3	WB	109-5	21-31-11	D40242P	A05			D10728	H			YR320-YR328

WIRE LIST

D280A108

91-21-11

Section W6100

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6102	286A6102				CABIN PRESSURE OUTFLOW VALVE TO E/E BAY (LA2) (continued)										
3002R	24	Y3	WB		0-0	21-31-11	D40242P	A04			D10728	F			ALL
3002Y	24	Y3	WB		0-0	21-31-11	D40242P	A06			D10728	G			ALL
3002Z			WB		0-0	21-31-11	D40242P	PERG	1F		GD03738	ST..	1		ALL
5501	20	PA			103-6	21-31-22	D40240P	A01			D10732	K			YC051-YC055
5501	20	PA			104-4	21-31-22	D40240P	A01			D10732	K			YC056-YL999, YR301-YR319
5501	20	PA			85-0	21-31-22	D40240P	A01			D10732	K			YN231-YN501
5501	20	PA			107-2	21-31-22	D40240P	A01			D10732	K			YR320-YR328
5502	24	PK			103-6	21-31-22	D40240P	A07			D10732	C-			YC051-YC055
5502	24	PK			104-4	21-31-22	D40240P	A07			D10732	C-			YC056-YL999, YR301-YR319
5502	24	PK			85-0	21-31-22	D40240P	A07			D10732	C-			YN231-YN501
5502	24	PK			107-2	21-31-22	D40240P	A07			D10732	C-			YR320-YR328
5503	20	PA			1-6	21-31-22	D10728	J			GD03738	ST..	1		YC051-YC055
5503	20	PA			1-9	21-31-22	D10728	J			GD03738	ST..	1		YC056-YR328
5504	20	PA			3-0	21-31-22	D10732	G			GD03738	ST..	1		YC051-YC055
5504	20	PA			3-11	21-31-22	D10732	G			GD03738	ST..	1		YC056-YR328
5505	20	PA			3-0	21-31-22	D10732	B-			GD03738	DC..	1		YC051-YC055
5505	20	PA			3-11	21-31-22	D10732	B-			GD03738	DC..	1		YC056-YR328
5506	20	PA			3-0	21-31-22	D10732	J			GD03738	DC..	1		YC051-YC055
5506	20	PA			3-11	21-31-22	D10732	J			GD03738	DC..	1		YC056-YR328
5507	20	CQ			2-7	21-31-11	D10730	D			GD03738	ST..	1		YC051-YC055
5507	20	CQ			2-8	21-31-11	D10730	D			GD03738	ST..	1		YC056-YR328

WIRE LIST

D280A108

91-21-11
Section W6100
Page 2 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6110 286A6110 P91 (FWD DISC) TO E/E BAY																
0001		20		PA		23-10	33-34-11	S00084		1	C	SM00001		S		YC051-YD158
0001		20		PA		24-6	33-34-11	S00084		1	C	SM00001		S		YD160-YR328
0002		20		PA		18-5	33-34-11	SP00394			S	S00084	2	C		ALL
0003		20		PA		7-10	33-34-11	SP00394			S	SP00390		S		ALL
0004		20		PA		9-7	33-34-11	SP00392			S	SP00390		S		ALL
0005		20		PA		2-9	33-34-11	GD05010	AC..		E	L00199	=G	C		ALL
0006		20		PA		8-1	33-34-11	GD05014	AC..		E	L00200	=G	C		YC051-YC064
0006		20		PA		1-11	33-34-11	GD00475	AC..		E	L00200	=G	C		YC065-YR328
0007		20		PA		3-10	33-34-11	GD05014	AC..		E	L00201	=G	C		ALL
0009		20		PA		1-3	33-34-11	D11418		6		SM00001		S		ALL
0010		20		PA		9-0	33-34-11	S00085		1	C	SM00001		S		YC051-YC055
0010		20		PA		8-11	33-34-11	S00085		1	C	SM00001		S		YC056-YD158
0010		20		PA		9-5	33-34-11	S00085		1	C	SM00001		S		YD160-YR328
0011		20		PA		18-6	SPARE	D40364P	B05			D11418	CAP	Y		YC051-YD158
0011		20		PA		19-1	SPARE	D40364P	B05			D11418	CAP	Y		YD160-YR328
0012		20		PA		18-6	SPARE	D40364P	B06			D11418	CAP	Y		YC051-YD158
0012		20		PA		19-1	SPARE	D40364P	B06			D11418	CAP	Y		YD160-YR328
0013		20		PA		18-6	SPARE	D40364P	A06			D11418	CAP	Y		YC051-YD158
0013		20		PA		19-1	SPARE	D40364P	A06			D11418	CAP	Y		YD160-YR328
0014		22		PA		25-7	25-51-21	D11418		14		D40368P		14		YC051-YD158
0014		22		PA		26-3	25-51-21	D11418		14		D40368P		14		YD160-YL999, YR301-YR328
0020		20		PA		18-10	33-34-11	SP00102			S	S00085	2	C		YC051-YC055
0020		20		PA		18-2	33-34-11	SP00102			S	S00085	2	C		YC056-YD158
0020		20		PA		18-5	33-34-11	SP00102			S	S00085	2	C		YD160-YR328
0030		20		PA		7-1	33-34-11	SP00102			S	SP00104		S		YC051-YC055
0030		20		PA		7-3	33-34-11	SP00102			S	SP00104		S		YC056-YR328
0033		22		PA		18-6	25-51-21	D11418		3		D40364P	A01			YC051-YD158
0033		22		PA		19-1	25-51-21	D11418		3		D40364P	A01			YD160-YL999, YR301-YR328
0040		20		PA		14-9	33-34-11	SM00002			S	SP00104		S		YC051-YC055
0040		20		PA		4-10	33-34-11	SM00002			S	SP00104		S		YC056-YR328
0050		20		PA		12-11	33-34-11	GD03200	AC..	1A		L00202	=G	C		YC051-YC055
0050		20		PA		12-3	33-34-11	GD03200	AC..	1A		L00202	=G	C		YC056-YD158
0050		20		PA		12-5	33-34-11	GD03200	AC..	1A		L00202	=G	C		YD160-YR328
0060		20		PA		14-11	33-34-11	GD03200	AC..	1A		L00203	=G	C		YC051-YD158
0060		20		PA		15-1	33-34-11	GD03200	AC..	1A		L00203	=G	C		YD160-YR328
0070		20		PA		1-6	33-34-11	GD05018	AC..		E	L01307		B	C	ALL
0071		20		PA		11-3	33-34-11	SM00002			S	L01307		A	C	YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W6110

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6110	286A6110			P91 (FWD DISC) TO E/E BAY (continued)											
0071	20	PA			20-8	33-34-11	SM00002		S		L01307	A	C		YC056-YD158
0071	20	PA			20-11	33-34-11	SM00002		S		L01307	A	C		YD160-YR328
0072	20	PA			9-3	33-34-11	SM00002		S		L01313	A	C		YC051-YC055
0072	20	PA			14-2	33-34-11	SM00002		S		L01313	A	C		YC056-YR328
0073	20	PA			1-2	33-34-11	GD05016	AC..	E		L01313	B	C		ALL
0203	20	GA			32-0	27-25-11	D11939	X2			D40364P	A02			YC051-YD153
0203	20	PA			19-3	27-25-11	D40368P	21			D40364P	A02			YD154-YR328
0204	20	GA			32-0	27-25-11	D11941	X2			D40364P	B01			YC051-YD153
0204	20	PA			19-3	27-25-11	D40368P	22			D40364P	B01			YD154-YR328
0205	20	CQ			19-3	21-31-23	D40368P	23			D40364P	A09			YD158-YR328
0206	24	B6			19-3	21-31-23	D40368P	24			D40364P	A10			YD158-YR328
0501	22	PA			18-9	24-22-11	D11418	21			D48124P	A05			YC051-YD158
0501	22	PA			19-5	24-22-11	D11418	21			D48124P	A05			YD160-YR328
0503	24	PK			18-6	24-32-11	D11418	10			D40364P	A08			YC051-YD158
0503	24	PK			19-1	24-32-11	D11418	10			D40364P	A08			YD160-YR328
0504	24	PK			25-7	24-32-11	D11418	24			D40368P	3			YC051-YD158
0504	24	PK			26-3	24-32-11	D11418	24			D40368P	3			YD160-YR328
0505	20	HA			25-7	24-32-11	D11418	18			D40368P	4			YC051-YD158
0505	20	HA			26-3	24-32-11	D11418	18			D40368P	4			YD160-YR328
0506	18	PA			13-4	24-32-11	D11422	1			D11450	I			YC051-YD158, YN231-YN501
0506	18	PA			13-0	24-32-11	D11422	1			D11450	I			YD160-YL999, YR301-YR328
0507	18	PA			13-4	24-32-11	D11422	5			D11450	B			YC051-YD158, YN231-YN501
0507	18	PA			13-0	24-32-11	D11422	5			D11450	B			YD160-YL999, YR301-YR328
0508	22	PA			18-9	24-28-11	D11418	19			D48124P	A06			YC051-YD158
0508	22	PA			19-5	24-28-11	D11418	19			D48124P	A06			YD160-YR328
0509	22	PA			18-9	24-28-11	D11418	17			D48124P	A07			YC051-YD158
0509	22	PA			19-5	24-28-11	D11418	17			D48124P	A07			YD160-YR328
0510	18	PA			13-4	24-32-11	D11422	6			D11450	C			YC051-YD158, YN231-YN501
0510	18	PA			13-0	24-32-11	D11422	6			D11450	C			YD160-YL999, YR301-YR328
0511	22	CQ			19-5	29-11-12	D11418	22			D48124P	A10			ALL
0512	22	CQ			19-5	29-11-12	D11418	12			D48124P	B01			ALL
0513	22	PA			25-7	24-23-51	D11418	13			D40368P	1			YC051-YD158
0513	22	PA			26-3	24-23-51	D11418	13			D40368P	1			YD160-YR328

WIRE LIST

D280A108

91-21-11

Section W6110

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6110		286A6110			P91 (FWD DISC) TO E/E BAY (continued)											
0514		20		PA		12-6	27-53-11	D40364P	B07			D48124P	B08			YC051-YC055
0514		20		PA		12-5	27-53-11	D40364P	B07			D48124P	B08			YC056-YR328
0516		20		PA		4-1	24-51-11	D11418	16			GD03200	DC..	1A		YC051-YD158
0516		20		PA		4-6	24-51-11	D11418	16			GD03200	DC..	1A		YD160-YR328
0517		10		CQ		5-0	24-53-11	D11450	D			T00006	LV1	E		YC051-YC064
0517		10		CQ		5-7	24-53-11	D11450	D			T00006	LV1	E		YC065-YR328
0518		08		CQ		2-7	24-53-11	T00006	G	E		GD00010	AC..	F		YC051-YC064
0518		08		CQ		3-4	24-53-11	T00006	G	E		GD00010	AC..	F		YC065-YR328
0519		24		PK		19-4	24-32-11	D40368P	2			D40364P	A03			YC051-YC055
0519		24		PK		19-3	24-32-11	D40368P	2			D40364P	A03			YC056-YR328
0520		22		PA		19-4	SPARE	D40368P	5			D40364P	A04			YC051-YC055
0520		22		PA		19-3	SPARE	D40368P	5			D40364P	A04			YC056-YR328
0521		22		PA		19-4	SPARE	D40368P	6			D40364P	B03			YC051-YC055
0521		22		PA		19-3	SPARE	D40368P	6			D40364P	B03			YC056-YR328
0523		22		PA		19-4	27-81-11	D40368P	8			D40364P	A05			YC051-YC055
0523		22		PA		19-3	27-81-11	D40368P	8			D40364P	A05			YC056-YR328
0524		22		PA		19-4	27-83-11	D40368P	9			D40364P	B08			YC051-YC055
0524		22		PA		19-3	27-83-11	D40368P	9			D40364P	B08			YC056-YR328
0525		20		PA		12-6	27-53-11	D40364P	B09			D48124P	A08			YC051-YC055
0525		20		PA		12-5	27-53-11	D40364P	B09			D48124P	A08			YC056-YL999,
																YR301-YR328
0525		20		PA		12-2	27-53-11	D40364P	B09			D48124P	A08			YN231-YN501
0526		20		PA		12-6	27-53-11	D40364P	B10			D48124P	A09			YC051-YC055
0526		20		PA		12-5	27-53-11	D40364P	B10			D48124P	A09			YC056-YL999,
																YR301-YR328
0526		20		PA		12-2	27-53-11	D40364P	B10			D48124P	A09			YN231-YN501
5501		22		PA		18-9	21-27-21	D11418	15			D48124P	A01			YC051-YD158
5501		22		PA		19-5	21-27-21	D11418	15			D48124P	A01			YD160-YR328
5502		22		CQ		18-9	21-27-21	D11418	11			D48124P	A03			YC051-YD158
5502		22		CQ		19-5	21-27-21	D11418	11			D48124P	A03			YD160-YR328
5503		20		PA		11-3	21-27-21	D11422	2			D00160	1			YC051-YD158
5503		20		PA		10-11	21-27-21	D11422	2			D00160	1			YD160-YR328
5504		20		PA		11-3	21-27-21	D11422	3			D00160	2			YC051-YD158
5504		20		PA		10-11	21-27-21	D11422	3			D00160	2			YD160-YR328
5505		20		PA		11-3	21-27-21	D11422	4			D00160	3			YC051-YD158
5505		20		PA		10-11	21-27-21	D11422	4			D00160	3			YD160-YR328
5506		20		PA		4-2	21-27-21	D00160	7			GD01008	ST..	1A		ALL
5507		22		PA		11-3	21-27-21	D11422	7			D00160	5			YC051-YD158
5507		22		PA		10-11	21-27-21	D11422	7			D00160	5			YD160-YR328

WIRE LIST

D280A108

91-21-11

Section W6110

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6110	286A6110				P91 (FWD DISC) TO E/E BAY (continued)											
5508	20		PA		26-2	21-27-21		D00160		6		D48124P		A02		YC051-YD158
5508	20		PA		26-5	21-27-21		D00160		6		D48124P		A02		YD160-YR328
5509	20		PA		1-8	21-42-11		SM00006			9	D10884		3		YC051-YC055
5509	20		PA		1-7	21-42-11		SM00006			9	D10884		3		YC056-YR328
5510	20		PA		1-8	21-42-11		SM00004			9	D10884		1		YC051-YC055
5510	20		PA		1-7	21-42-11		SM00004			9	D10884		1		YC056-YR328
5513	20		PA		3-2	21-42-11		D10884		4		GD01914	ST..	E		ALL
5514	24		PK		18-9	21-42-11		D11418		4		D48124P		A04		YC051-YD158
5514	24		PK		19-5	21-42-11		D11418		4		D48124P		A04		YD160-YR328
5515	20		PA		18-1	21-42-11		D11418		1		SM00006			9	YC051-YC055
5515	20		PA		18-3	21-42-11		D11418		1		SM00006			9	YC056-YD158
5515	20		PA		18-11	21-42-11		D11418		1		SM00006			9	YD160-YR328
5516	20		PA		18-1	21-42-11		D11418		5		SM00004			9	YC051-YC055
5516	20		PA		18-3	21-42-11		D11418		5		SM00004			9	YC056-YD158
5516	20		PA		18-11	21-42-11		D11418		5		SM00004			9	YD160-YR328
5517	20		PA		2-2	21-42-11		SM00004			9	D48124P		B02		YC051-YC055
5517	20		PA		2-3	21-42-11		SM00004			9	D48124P		B02		YC056-YR328
5518	20		PA		2-2	21-42-11		SM00006			9	D48124P		B03		YC051-YC055
5518	20		PA		2-3	21-42-11		SM00006			9	D48124P		B03		YC056-YR328
A-A					0-0	33-34-11		SP00394			S	L00199		P		ALL
A-B					0-0	33-34-11		SP00392			S	L00200		P		ALL
A-C					0-0	33-34-11		SP00390			S	L00201		P		ALL
B-A					0-0	33-34-11		SP00102			S	L00202		P		ALL
B-B					0-0	33-34-11		SP00104			S	L00203		P		ALL

WIRE LIST

D280A108

91-21-11
Section W6110
Page 4 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W6122	286A6122				DISC AB0500DR TO MAIN WHEEL WELL											
0501	22		PA		20-2	29-32-11		D40410P	1			D46042J	4			YC051-YD158
0501	22		PA		20-3	29-32-11		D40410P	1			D46042J	4			YD160-YL999, YR301-YR328
0501	22		PA		20-1	29-32-11		D40410P	1			D46042J	4			YN231-YN501
0502	22		PA		20-2	29-32-11		D40410P	2			D46042J	3			YC051-YD158
0502	22		PA		20-3	29-32-11		D40410P	2			D46042J	3			YD160-YL999, YR301-YR328
0502	22		PA		20-1	29-32-11		D40410P	2			D46042J	3			YN231-YN501
0504	20		CQ		20-2	29-11-11		D40400P	1			D46042J	6			YC051-YL999, YR301-YR328
0504	20		CQ		19-10	29-11-11		D40400P	1			D46042J	6			YN231-YN501
0505	20		CQ		20-2	29-11-11		D40400P	2			D46042J	7			YC051-YL999, YR301-YR328
0505	20		CQ		19-10	29-11-11		D40400P	2			D46042J	7			YN231-YN501
0506	22		PA		20-2	29-33-11		D40400P	5			D46042J	2			YC051-YL999, YR301-YR328
0506	22		PA		19-10	29-33-11		D40400P	5			D46042J	2			YN231-YN501
0507	22		PA		20-2	29-33-11		D40400P	6			D46042J	1			YC051-YL999, YR301-YR328
0507	22		PA		19-10	29-33-11		D40400P	6			D46042J	1			YN231-YN501
0508	20		PA		67-4	29-31-11		D40004J	12			SP00472		S		YC051-YL999, YR301-YR328
0508	20		PA		57-4	29-31-11		D40004J	12			SP00472		S		YN231-YN501
0509	20		PA		67-4	29-31-11		D40004J	14			SP00474		S		YC051-YL999, YR301-YR328
0509	20		PA		57-4	29-31-11		D40004J	14			SP00474		S		YN231-YN501
0510	20		PA		67-4	29-31-11		D40004J	13			SP00476		S		YC051-YL999, YR301-YR328
0510	20		PA		57-4	29-31-11		D40004J	13			SP00476		S		YN231-YN501
0513	20		PA		67-4	29-23-11		D40004J	15			SP00478		S		YC051-YL999, YR301-YR328
0513	20		PA		57-4	29-23-11		D40004J	15			SP00478		S		YN231-YN501
0515	22		CQ		20-2	31-62-24		D40400P	3			D46042J	8			YC051-YL999, YR301-YR328
0515	22		CQ		19-10	31-62-24		D40400P	3			D46042J	8			YN231-YN501
1101R	20		X5	BN	20-2	26-12-11		D46042J	9			D40410P	14			YC051-YD158
1101R	20		X5	BN	20-3	26-12-11		D46042J	9			D40410P	14			YD160-YL999, YR301-YR328
1101R	20		X5	BN	20-1	26-12-11		D46042J	9			D40410P	14			YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W6120

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6122	286A6122				DISC AB0500DR TO MAIN WHEEL WELL (continued)										
1101Z				BN	0-0	26-12-11	D46042J	DED			D40410P	DED			ALL
2211B	22	X2		KK	24-8	32-41-11	D40004J	4			D40410P	4			YC051-YD158
2211B	22	X2		KK	24-9	32-41-11	D40004J	4			D40410P	4			YD160-YL999, YR301-YR328 YN231-YN501
2211B	22	X2		KK	24-7	32-41-11	D40004J	4			D40410P	4			ALL
2211R	22	X2		KK	0-0	32-41-11	D40004J	3			D40410P	3			ALL
2211Z				KK	0-0	32-41-11	D40004J	5			D40410P	5			ALL
2223B	22	PB		KX	24-8	32-64-12	D40410P	7			D40004J	7			YC051-YD158
2223B	22	PB		KX	24-9	32-64-12	D40410P	7			D40004J	7			YD160-YL999, YR301-YR328 YN231-YN501
2223B	22	PB		KX	24-7	32-64-12	D40410P	7			D40004J	7			ALL
2223R	22	PB		KX	0-0	32-64-12	D40410P	6			D40004J	6			YC051-YD158
2224B	22	PB		KY	24-8	32-64-12	D40410P	9			D40004J	2			YD160-YL999, YR301-YR328 YN231-YN501
2224B	22	PB		KY	24-9	32-64-12	D40410P	9			D40004J	2			ALL
2224B	22	PB		KY	24-7	32-64-12	D40410P	9			D40004J	2			YC051-YD158
2224R	22	PB		KY	0-0	32-64-12	D40410P	8			D40004J	1			YD160-YL999, YR301-YR328 YN231-YN501
2241B	22	PB		LQ	24-8	32-31-12	D40410P	11			D40004J	10			ALL
2241B	22	PB		LQ	24-9	32-31-12	D40410P	11			D40004J	10			YC051-YD158
2241B	22	PB		LQ	24-7	32-31-12	D40410P	11			D40004J	10			YD160-YL999, YR301-YR328 YN231-YN501
2241R	22	PB		LQ	0-0	32-31-12	D40410P	10			D40004J	9			ALL
6011	20	CQ			10-4	28-21-11	SP00458	S			D46042J	5			ALL
W6124	286A6124				MAIN WHEEL WELL TO AB0500DR AND CROWN										
0001	20	PA			24-10	33-25-11	D40404P	11			D40006J	2			ALL
0030	20	PA			20-4	31-31-15	D46038J	3			D40404P	3			YC065-YD158, YN231-YN501 YD160-YL999, YR301-YR328
0030	20	PA			20-5	31-31-15	D46038J	3			D40404P	3			YC051-YD158
0501	20	PA			20-4	27-23-11	D40402P	3			D46038J	13			YD160-YL999, YR301-YR328 YN231-YN501
0501	20	PA			20-5	27-23-11	D40402P	3			D46038J	13			YC051-YD158
0501	20	PA			20-0	27-23-11	D40402P	3			D46038J	13			YD160-YL999, YR301-YR328 YN231-YN501
0502	20	PA			20-4	27-23-11	D40402P	4			D46038J	14			YC051-YD158
0502	20	PA			20-5	27-23-11	D40402P	4			D46038J	14			YD160-YL999, YR301-YR328 YN231-YN501
0502	20	PA			20-0	27-23-11	D40402P	4			D46038J	14			ALL
0503	22	PA			28-7	27-23-14	D40262P	14			D46038J	10			YC051-YD158

WIRE LIST

D280A108

91-21-11

Section W6120

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6124		286A6124			MAIN WHEEL WELL TO AB0500DR AND CROWN (continued)											
0503		22		PA		29-0	27-23-14	D40262P		14		D46038J		10		YD160-YL999
0503		22		PA		28-3	27-23-14	D40262P		14		D46038J		10		YN231-YN260
0503		22		PA		28-1	27-23-14	D43400P		14		D46038J		10		YN501
0503		22		PA		28-4	27-23-14	D43400P		14		D46038J		10		YR301-YR328
0504		22		PA		24-0	27-23-11	D40262P		12		D46040J		5		YC051-YL999
0504		22		PA		24-9	27-23-11	D40262P		12		D46040J		5		YN231-YN260
0504		22		PA		23-1	27-23-11	D43400P		12		D46040J		5		YN501
0504		22		PA		23-3	27-23-11	D43400P		12		D46040J		5		YR301-YR328
0505		22		PA		24-0	27-23-11	D40262P		13		D46040J		15		YC051-YL999
0505		22		PA		24-9	27-23-11	D40262P		13		D46040J		15		YN231-YN260
0505		22		PA		23-1	27-23-11	D43400P		13		D46040J		15		YN501
0505		22		PA		23-3	27-23-11	D43400P		13		D46040J		15		YR301-YR328
0506		20		PA		24-5	27-31-11	SP00542			S	D46040J		12		YC051-YC057
0506		20		PA		13-10	27-31-11	SP00542			S	D46040J		12		YC058-YL999,
																YR301-YR328
0506		20		PA		13-9	27-31-11	SP00542			S	D46040J		12		YN231-YN501
0507		20		CQ		46-2	27-31-11	D40404P		7		D40264P		5		YC051-YC055
0507		20		CQ		45-9	27-31-11	D40404P		7		D40262P		18		YC056-YD158
0507		20		CQ		45-10	27-31-11	D40404P		7		D40262P		18		YD160-YL999
0507		20		CQ		45-4	27-31-11	D40404P		7		D40262P		18		YN231-YN260
0507		20		CQ		44-10	27-31-11	D40404P		7		D43400P		18		YN501
0507		20		CQ		45-1	27-31-11	D40404P		7		D43400P		18		YR301-YR328
0508		20		PA		24-5	27-31-11	D40264P		9		D46040J		13		YC051-YC053
0509		20		PA		24-0	27-53-11	D40262P		1		D46040J		16		YC051-YL999
0509		20		PA		24-9	27-53-11	D40262P		1		D46040J		16		YN231-YN260
0509		20		PA		23-1	27-53-11	D43400P		1		D46040J		16		YN501
0509		20		PA		23-3	27-53-11	D43400P		1		D46040J		16		YR301-YR328
0510		20		PA		24-0	27-53-11	D40262P		2		D46040J		17		YC051-YL999
0510		20		PA		24-9	27-53-11	D40262P		2		D46040J		17		YN231-YN260
0510		20		PA		23-1	27-53-11	D43400P		2		D46040J		17		YN501
0510		20		PA		23-3	27-53-11	D43400P		2		D46040J		17		YR301-YR328
0511		20		PA		24-0	27-53-11	D40262P		3		D46040J		7		YC051-YL999
0511		20		PA		24-9	27-53-11	D40262P		3		D46040J		7		YN231-YN260
0511		20		PA		23-1	27-53-11	D43400P		3		D46040J		7		YN501
0511		20		PA		23-3	27-53-11	D43400P		3		D46040J		7		YR301-YR328
0518		20		PA		23-11	27-53-12	D40262P		16		D46044J		13		YC051-YL999
0518		20		PA		23-6	27-53-12	D40262P		16		D46044J		13		YN231-YN260
0518		20		PA		23-0	27-53-12	D43400P		16		D46044J		13		YN501
0518		20		PA		23-2	27-53-12	D43400P		16		D46044J		13		YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W6120

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type
W6124	286A6124			MAIN WHEEL WELL TO AB0500DR AND CROWN (continued)										
0519	20	PA		23-11	27-53-12	D40262P		17			D46044J	12		YC051-YL999
0519	20	PA		23-6	27-53-12	D40262P		17			D46044J	12		YN231-YN260
0519	20	PA		23-0	27-53-12	D43400P		17			D46044J	12		YN501
0519	20	PA		23-2	27-53-12	D43400P		17			D46044J	12		YR301-YR328
0520	22	PA		24-9	27-54-11	D40402P		23			D46044J	3		YC051-YD158
0520	22	PA		24-10	27-54-11	D40402P		23			D46044J	3		YD160-YL999, YR301-YR328
0520	22	PA		24-7	27-54-11	D40402P		23			D46044J	3		YN231-YN501
0523	22	CQ		20-4	29-23-11	D40402P		24			D46038J	8		YC051-YD158
0523	22	CQ		20-5	29-23-11	D40402P		24			D46038J	8		YD160-YL999, YR301-YR328
0523	22	CQ		20-0	29-23-11	D40402P		24			D46038J	8		YN231-YN501
0524	22	PA		20-4	29-23-11	D40402P		15			D46038J	11		YC051-YD158
0524	22	PA		20-5	29-23-11	D40402P		15			D46038J	11		YD160-YR328
0526	22	PA		6-8	31-53-11	GD00662		DC..	1A		D46038J	4		YC051-YC057
0526	22	PA		6-9	31-53-11	GD00662		DC..	1A		D46038J	4		YC058-YD158
0526	22	PA		7-2	31-53-11	GD00662		DC..	1A		D46038J	4		YD160-YR328
0527	20	PA		13-10	27-31-11	D46040J		13			SP00503		S	YC054-YL999, YR301-YR328
0527	20	PA		13-9	27-31-11	D46040J		13			SP00503		S	YN231-YN501
0528	20	PA		14-7	27-31-11	D40264P		9			SP00505		S	YC054-YL999, YR301-YR328
0528	20	PA		14-4	27-31-11	D40264P		9			SP00505		S	YN231-YN260
0528	20	PA		14-6	27-31-11	D40264P		9			SP00505		S	YN501
0529	22	PA		10-2	29-25-11	D46602P		5			D46038J	9		YC051-YD158
0529	22	PA		10-7	29-25-11	D46602P		5			D46038J	9		YD160-YL999, YR301-YR328
0529	22	PA		10-8	29-25-11	D46602P		5			D46038J	9		YN231-YN501
0530	18	PA		5-1	29-25-11	D46602P		6			D46040J	2		YC051-YL999, YR301-YR328
0530	18	PA		5-11	29-25-11	D46602P		6			D46040J	2		YN231-YN501
0531	18	PA		5-1	29-25-11	D46602P		7			D46040J	9		YC051-YL952
0531	18	PA		5-11	29-25-11	D46602P		7			D46040J	9		YN231-YN501
0532	22	PA		0-7	29-25-11	D46040J		18			D46040J	19		YC051-YL952, YN231-YN501
0532	22	PA		5-1	29-25-11	D46040J		18			D46602P	7		YL953-YL999, YR301-YR328
0533	18	PA		19-9	29-25-11	TB0205W	A009	1			D46040J	1		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W6120

Page 4

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	
W6124	286A6124			MAIN WHEEL WELL TO AB0500DR AND CROWN (continued)										
0533	18	PA		20-1	29-25-11	TB0205W		A009	1		D46040J	1		YN231-YN501
0534	18	PA		19-9	29-25-11	TB0205W		A009	1		D46040J	6		YC051-YL952
0534	18	PA		20-1	29-25-11	TB0205W		A009	1		D46040J	6		YN231-YN501
0535	18	PA		22-3	29-25-11	TB0205W		A009	1		D46602P	8		YC051-YL999, YR301-YR328
0535	18	PA		23-4	29-25-11	TB0205W		A009	1		D46602P	8		YN231-YN501
0536	18	PA		22-5	29-25-11	TB0205V		A013	1		D46602P	9		YC051-YD158
0536	18	PA		22-6	29-25-11	TB0205V		A013	1		D46602P	9		YD160-YL999, YR301-YR328
0536	18	PA		23-6	29-25-11	TB0205V		A013	1		D46602P	9		YN231-YN501
0539	22	PA		24-0	27-23-11	D40262P			19		D46040J	3		YC051-YC057
0539	22	PA		24-0	SPARE	D40262P			19		D46040J	3		YC058-YD158
0541	22	PA		24-9	27-54-11	D40402P			22		D46044J	14		YC051-YD158
0541	22	PA		24-10	27-54-11	D40402P			22		D46044J	14		YD160-YL999, YR301-YR328
0541	22	PA		24-7	27-54-11	D40402P			22		D46044J	14		YN231-YN501
0542	20	PA		20-4	27-61-11	D40402P			17		D46038J	15		YC051-YD158
0542	20	PA		20-5	27-61-11	D40402P			17		D46038J	15		YD160-YL999, YR301-YR328
0542	20	PA		20-0	27-61-11	D40402P			17		D46038J	15		YN231-YN501
0543	20	PA		20-4	27-61-11	D40402P			18		D46038J	27		YC051-YD158
0543	20	PA		20-5	27-61-11	D40402P			18		D46038J	27		YD160-YL999, YR301-YR328
0543	20	PA		20-0	27-61-11	D40402P			18		D46038J	27		YN231-YN501
0545	20	PA		28-7	27-81-51	D46038J			19		D40262P	4		YC051-YD158
0545	20	PA		29-0	27-81-51	D46038J			19		D40262P	4		YD160-YL999
0545	20	PA		28-0	27-81-51	D46038J			19		D40262P	4		YN231-YN260
0545	20	PA		28-1	27-81-51	D46038J			19		D43400P	4		YN501
0545	20	PA		28-4	27-81-51	D46038J			19		D43400P	4		YR301-YR328
0546	20	PA		28-7	27-81-51	D46038J			23		D40262P	5		YC051-YD158
0546	20	PA		29-0	27-81-51	D46038J			23		D40262P	5		YD160-YL999
0546	20	PA		28-0	27-81-51	D46038J			23		D40262P	5		YN231-YN260
0546	20	PA		28-1	27-81-51	D46038J			23		D43400P	5		YN501
0546	20	PA		28-4	27-81-51	D46038J			23		D43400P	5		YR301-YR328
0550	22	PA		24-10	22-23-12	D40404P			5		D40006J	1		ALL
0553	22	CQ		24-10	32-64-21	D40404P			26		D46040J	10		ALL
0561	22	CQ		24-10	32-64-21	D40404P			14		D46040J	8		ALL
0562	20	GK		17-0	27-31-37	D40262P			21		SP00536		S	YC051-YC057
0562	24	PK		14-2	27-31-37	D40262P			21		SP00536		S	YC058-YL999

WIRE LIST

D280A108

91-21-11

Section W6120

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W6124	286A6124				MAIN WHEEL WELL TO AB0500DR AND CROWN (continued)										
0562	24		PK		13-10	27-31-37	D40262P		21		SP00536		S		YN231-YN260
0562	24		PK		13-4	27-31-37	D43400P		21		SP00536		S		YN501
0562	24		PK		13-5	27-31-37	D43400P		21		SP00536		S		YR301-YR328
0563	20		PA		17-0	27-31-37	D40262P		20		SP00538		S		YC051-YC057
0563	20		PA		14-2	27-31-37	D40262P		20		SP00538		S		YC058-YL999
0563	20		PA		13-10	27-31-37	D40262P		20		SP00538		S		YN231-YN260
0563	20		PA		13-4	27-31-37	D43400P		20		SP00538		S		YN501
0563	20		PA		13-5	27-31-37	D43400P		20		SP00538		S		YR301-YR328
0564	20		GK		17-0	27-31-37	D40262P		15		SP00540		S		YC051-YC057
0564	24		PK		14-2	27-31-37	D40262P		15		SP00540		S		YC058-YL999
0564	24		PK		13-10	27-31-37	D40262P		15		SP00540		S		YN231-YN260
0564	24		PK		13-4	27-31-37	D43400P		15		SP00540		S		YN501
0564	24		PK		13-5	27-31-37	D43400P		15		SP00540		S		YR301-YR328
0565	20		PA		17-0	27-31-11	D40264P		8		SP00542		S		YC051-YC057
0565	20		PA		14-7	27-31-11	D40264P		8		SP00542		S		YC058-YL999, YR301-YR328
0565	20		PA		14-4	27-31-11	D40264P		8		SP00542		S		YN231-YN260
0565	20		PA		14-6	27-31-11	D40264P		8		SP00542		S		YN501
0566	18		PA		25-10	29-25-11	D40264P		3		D46602P	1			YC051-YL999, YR301-YR328
0566	18		PA		26-7	29-25-11	D40264P		3		D46602P	1			YN231-YN501
0567	18		PA		25-10	29-25-11	D40264P		4		D46602P	2			YC051-YL999, YR301-YR328
0567	18		PA		26-7	29-25-11	D40264P		4		D46602P	2			YN231-YN501
0568	18		PA		22-5	29-25-11	TB0205V	A015	1		D46602P	3			YC051-YD158
0568	18		PA		22-6	29-25-11	TB0205V	A015	1		D46602P	3			YD160-YL999, YR301-YR328
0568	18		PA		23-6	29-25-11	TB0205V	A015	1		D46602P	3			YN231-YN501
0575	20		PA		18-7	27-53-11	D46020J		1		D40262P	8			YC051-YD158
0575	20		PA		18-7	27-53-11	D46020J		7		D40262P	8			YD160-YL999
0575	20		PA		18-5	27-53-11	D46020J		7		D40262P	8			YN231-YN260
0575	20		PA		17-9	27-53-11	D46020J		7		D43400P	8			YN501
0575	20		PA		17-11	27-53-11	D46020J		7		D43400P	8			YR301-YR328
0576	20		PA		8-6	27-53-11	D46020J		4		SP00634		S		ALL
0577	20		PA		14-2	27-53-11	SP00634			S	D40262P	9			YC051-YL999
0577	20		PA		13-11	27-53-11	SP00634			S	D40262P	9			YN231-YN260
0577	20		PA		13-4	27-53-11	SP00634			S	D43400P	9			YN501
0577	20		PA		13-5	27-53-11	SP00634			S	D43400P	9			YR301-YR328
0578	20		PA		18-7	27-81-51	D46020J		5		D40262P	6			YC051-YL999

WIRE LIST

D280A108

91-21-11

Section W6120

Page 6

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W6124	286A6124				MAIN WHEEL WELL TO AB0500DR AND CROWN (continued)											
0578	20		PA		18-5	27-81-51		D46020J	5			D40262P	6			YN231-YN260
0578	20		PA		17-9	27-81-51		D46020J	5			D43400P	6			YN501
0578	20		PA		17-11	27-81-51		D46020J	5			D43400P	6			YR301-YR328
0579	20		PA		18-7	27-81-51		D46020J	6			D40262P	7			YC051-YL999
0579	20		PA		18-5	27-81-51		D46020J	6			D40262P	7			YN231-YN260
0579	20		PA		17-9	27-81-51		D46020J	6			D43400P	7			YN501
0579	20		PA		17-11	27-81-51		D46020J	6			D43400P	7			YR301-YR328
0580	22		PA		18-7	29-31-11		D46020J	2			D40262P	11			YC051-YL999
0580	22		PA		18-5	29-31-11		D46020J	2			D40262P	11			YN231-YN260
0580	22		PA		17-9	29-31-11		D46020J	2			D43400P	11			YN501
0580	22		PA		17-11	29-31-11		D46020J	2			D43400P	11			YR301-YR328
0581	20		PA		18-7	29-35-11		D46020J	3			D40262P	10			YC051-YL999
0581	20		PA		18-5	29-35-11		D46020J	3			D40262P	10			YN231-YN260
0581	20		PA		17-9	29-35-11		D46020J	3			D43400P	10			YN501
0581	20		PA		17-11	29-35-11		D46020J	3			D43400P	10			YR301-YR328
2201B	22		PB	KA	20-4	31-53-11		D40404P	12			D46038J	5			YC051-YD158, YN231-YN501
2201B	22		PB	KA	20-5	31-53-11		D40404P	12			D46038J	5			YD160-YL999, YR301-YR328
2201R	22		PB	KA	0-0	31-53-11		D40404P	4			D46038J	6			ALL
3001B	20		X3	BA	18-7	31-31-14		D40262P	23			D46020J	11			YD160-YL999
3001B	20		X3	BA	18-4	31-31-14		D40262P	23			D46020J	11			YN231-YN260
3001B	20		X3	BA	17-9	31-31-14		D43400P	23			D46020J	11			YN501
3001B	20		X3	BA	17-11	31-31-14		D43400P	23			D46020J	11			YR301-YR328
3001R	20		X3	BA	0-0	31-31-14		D40262P	22			D46020J	9			YD160-YN260
3001R	20		X3	BA	0-0	31-31-14		D43400P	22			D46020J	9			YN501-YR328
3001Y	20		X3	BA	0-0	31-31-14		D40262P	24			D46020J	12			YD160-YN260
3001Y	20		X3	BA	0-0	31-31-14		D43400P	24			D46020J	12			YN501-YR328
3001Z				BA	0-0	31-31-14		D40262P	19			D46020J	8			YD160-YN260
3001Z				BA	0-0	31-31-14		D43400P	19			D46020J	8			YN501-YR328
5501	22		HA		24-10	21-51-14		D40404P	9			D46040J	14			YC051-YD158
5501	20		VF	HA	24-10	21-51-14		D40404P	9			D46040J	14			YD160-YR328
5501Z				HA	0-0	21-51-14		D46040J	S/R			GD00662	ST..	1A		YD160-YR328
W6128	286A6128				E/E BAY TO MWW-SYS A ELEC HYD PUMP											
0001	20		HL		48-0	33-42-11		D00476	1			D43060P	1			YC051-YC055
0001	20		HL		47-11	33-42-11		D00476	1			D43060P	1			YC056-YD152

WIRE LIST

D280A108

91-21-11

Section W6120

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6128	286A6128				E/E BAY TO MWW-SYS A ELEC HYD PUMP (continued)											
0001	20		HL		48-1	33-42-11		D00476				D43060P	1			YD153-YL968, YR301-YR323, YR325-YR328
0001	20		HL		38-5	33-42-11		D00476				D43060P	1			YN231-YN236, YN501
0002	20		HL		48-0	33-42-11		D00476				D43060P	2			YC051-YC055
0002	20		HL		47-11	33-42-11		D00476				D43060P	2			YC056-YD152
0002	20		HL		48-1	33-42-11		D00476				D43060P	2			YD153-YL968, YR301-YR323, YR325-YR328
0002	20		HL		38-5	33-42-11		D00476				D43060P	2			YN231-YN236, YN501
0003	18		HL		48-0	33-42-11		D00476	3	18		D43060P	4			YC051-YC055
0003	18		HL		47-11	33-42-11		D00476	3	18		D43060P	4			YC056-YD152
0003	18		HL		48-1	33-42-11		D00476	3	18		D43060P	4			YD153-YL968, YR301-YR323, YR325-YR328
0003	18		HL		38-5	33-42-11		D00476	3	18		D43060P	4			YN231-YN236, YN501
0004	20		HL		1-11	33-42-11		D00476	4			GD00016	AC..	1		YC051-YC055, YD153-YL968, YN231-YN236, YN501-YR323, YR325-YR328
0004	20		HL		1-10	33-42-11		D00476	4			GD00016	AC..	1		YC056-YD152
0005	20		HL		1-11	33-42-11		D00476	5			GD00016	ST..	1		YC051-YC055, YD153-YL968, YN231-YN236, YN501-YR323, YR325-YR328
0005	20		HL		1-10	33-42-11		D00476	5			GD00016	ST..	1		YC056-YD152
0006	20		HL		0-7	33-42-11		D00476	6			D00476	7			YC051-YL968, YN231-YN236, YN501-YR323, YR325-YR328
0501	18		HA		4-8	29-11-12		D02664	5			GD00318	DC..	E	*1	YC051-YC055
0501	18		HA		4-6	29-11-12		D02664	5			GD00318	DC..	E	*1	YC056-YD152
0501	18		HA		4-5	29-11-12		D02664	5			GD00318	DC..	E	*1	YD153-YL968, YR301-YR323, YR325-YR328
0501	18		HA		5-0	29-11-12		D02664	5			GD00318	DC..	E	*1	YN231-YN236, YN501
0502	18		HA		3-2	29-34-11		D02664	7			SM00001		9		YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W6120

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W6128	286A6128				E/E BAY TO MWW-SYS A ELEC HYD PUMP (continued)												
0502	18		HA		3-0	29-34-11	D02664		7			SM00001		9		YC056-YD152	
0502	18		HA		3-1	29-34-11	D02664		7			SM00001		9		YD153-YL968, YN231-YN236, YN501-YR323, YR325-YR328	
0503	18		HA		65-8	29-11-12	D02664		4			SP00012		S		YC051-YD152	
0503	18		HA		64-0	29-11-12	D02664		4			SP00012		S		YD153-YL968, YR301-YR323, YR325-YR328	
0503	18		HA		55-11	29-11-12	D02664		4			SP00012		S		YN231-YN236, YN501	
0504	10		CQ		63-9	29-11-12	D02664		1	10		D11456	D			YC051-YD152	
0504	10		CQ		62-1	29-11-12	D02664		1	10		D11456	D			YD153-YL968, YR301-YR323, YR325-YR328	
0504	10		CQ		52-3	29-11-12	D02664		1	10		D11456	D			YN231-YN236, YN501	
0505	10		CQ		63-9	29-11-12	D02664		3	10		D11456	E			YC051-YD152	
0505	10		CQ		62-1	29-11-12	D02664		3	10		D11456	E			YD153-YL968, YR301-YR323, YR325-YR328	
0505	10		CQ		52-3	29-11-12	D02664		3	10		D11456	E			YN231-YN236, YN501	
0506	10		CQ		63-9	29-11-12	D02664		6	10		D11456	F			YC051-YD152	
0506	10		CQ		62-1	29-11-12	D02664		6	10		D11456	F			YD153-YL968, YR301-YR323, YR325-YR328	
0506	10		CQ		52-3	29-11-12	D02664		6	10		D11456	F			YN231-YN236, YN501	
0507	18		HA		1-8	29-34-11	D02688		B			SM00001		9		YC051-YC055	
0507	18		HA		1-5	29-34-11	D02688		B			SM00001		9		YC056-YD152	
0507	18		HA		1-11	29-34-11	D02688		B			SM00001		9		YD153-YL968, YN231-YN236, YN501-YR323, YR325-YR328	
0508	18		HA		3-2	29-34-11	D02688		A			GD00318	DC..	E	*1	YC051-YC055, YD153-YL968, YR301-YR323, YR325-YR328	
0508	18		HA		2-11	29-34-11	D02688		A			GD00318	DC..	E	*1	YC056-YD152	
0508	18		HA		3-9	29-34-11	D02688		A			GD00318	DC..	E	*1	YN231-YN236, YN501	
0509	18		HA		64-0	29-34-11	D43060P		7			SM00001		9		YC051-YC055	
0509	18		HA		64-1	29-34-11	D43060P		7			SM00001		9		YC056-YD152	

WIRE LIST

D280A108

91-21-11

Section W6120

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6128	286A6128				E/E BAY TO MWW-SYS A ELEC HYD PUMP (continued)											
0509	18		HA		62-4	29-34-11		D43060P	7			SM00001		9		YD153-YL968, YR301-YR323, YR325-YR328
0509	18		HA		52-6	29-34-11		D43060P	7			SM00001		9		YN231-YN236, YN501
6011	18		PA		24-2	28-21-11		SP00426		9		SP00318		S		YC051-YD152
6011	18		PA		21-4	28-21-11		SP00426		9		SP00318		S		YD153-YL968, YR301-YR323, YR325-YR328
6011	18		PA		21-2	28-21-11		SP00426		9		SP00318		S		YN231-YN236, YN501
YAAF					0-0	29-11-12		GD00016	ST..	1		GD02336	ST..	GW		YC051-YL968, YN231-YN236, YN501-YR323, YR325-YR328

WIRE LIST
D280A108

91-21-11
Section W6120
Page 10 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6134	286A6134			E/E BAY TO VERTICAL STAB											
0001	20		HL		112-2	27-25-11	D40194P	A20			D40268J	10			YC051-YC052
0001	20		PA		108-9	27-25-11	D40194P	A20			D40842P	1			YC053-YL999, YR301-YR328
0001	20		PA		89-11	27-25-11	D40194P	A20			D40842P	1			YN231-YN236, YN501
0002	20		HL		112-2	27-25-11	D40194P	B20			D40268J	11			YC051-YC052
0002	20		PA		108-9	27-25-11	D40194P	B20			D40842P	2			YC053-YL999, YR301-YR328
0002	20		PA		89-11	27-25-11	D40194P	B20			D40842P	2			YN231-YN236, YN501
0006	20		HL		108-2	33-49-11	D40192J	6			D40194P	B15			YC051-YC052
0006	20		PA		108-4	33-49-11	D40192J	6			D40194P	B15			YC053-YC055
0006	20		PA		108-5	33-49-11	D40192J	6			D40194P	B15			YC056-YL999, YR301-YR328
0006	20		PA		89-6	33-49-11	D40192J	6			D40194P	B15			YN231-YN236, YN501
0501	20		HL		113-9	27-21-11	D40238P	A01			D40268J	13			YC051-YC052
0501	20		PA		110-5	27-21-11	D40238P	A01			D40842P	3			YC053-YC055
0501	20		PA		110-4	27-21-11	D40238P	A01			D40842P	3			YC056-YL999, YR301-YR328
0501	20		PA		91-6	27-21-11	D40238P	A01			D40842P	3			YN231-YN236, YN501
0502	20		HL		112-2	27-21-11	D40194P	A19			D40268J	12			YC051-YC052
0502	20		PA		108-9	27-21-11	D40194P	A19			D40842P	4			YC053-YD153
0503	20		HL		112-2	27-21-11	D40194P	A04			D40268J	14			YC051-YC052
0503	20		PA		108-9	27-21-11	D40194P	A04			D40842P	5			YC053-YD153
0505	20		HL		112-2	27-28-11	D40194P	A05			D40268J	6			YC051-YC052
0505	20		PA		108-9	27-28-11	D40194P	A05			D40842P	6			YC053-YL999, YR301-YR328
0505	20		PA		89-11	27-28-11	D40194P	A05			D40842P	6			YN231-YN236, YN501
0506	20		HL		112-2	27-28-11	D40194P	A06			D40268J	7			YC051-YC052
0506	20		PA		108-9	27-28-11	D40194P	A06			D40842P	7			YC053-YL999, YR301-YR328
0506	20		PA		89-11	27-28-11	D40194P	A06			D40842P	7			YN231-YN236, YN501
0507	20		HL		10-5	27-31-37	SM00001		9		D00756	3			YC051-YC052
0507	20		PA		3-6	27-31-37	SM00001		9		D40842P	8			YC053-YN236, YN501-YR328
0508	20		HL		10-5	27-31-37	SM00001		9		D00756	1			YC051-YC052
0508	20		PA		3-6	27-31-37	SM00001		9		D40842P	9			YC053-YN236, YN501-YR328
0509	20		HL		10-5	27-31-37	SM00002		9		D00756	2			YC051-YC052
0509	20		PA		3-6	27-31-37	SM00002		9		D40842P	10			YC053-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W6130

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W6134	286A6134				E/E BAY TO VERTICAL STAB (continued)												
0510	20	HL		10-5	27-31-37	SM00002			9		D00756		4		YC051-YC052		
0510	20	PA		3-6	27-31-37	SM00002			9		D40842P		11		YC053-YN236, YN501-YR328		
0511	20	HL		100-11	27-31-37	TB0261X		A013	1A		D40262J		21		YC051-YC052		
0511	20	PA		100-11	27-31-37	TB0261X		A013	1A		D40262J		21		YC053-YC055		
0511	20	PA		63-4	27-31-37	TB0261X		A013	1A		D40262J		21		YC056-YL999		
0511	20	PA		53-8	27-31-37	TB0261X		A013	1A		D40262J		21		YN231-YN236		
0511	20	PA		54-2	27-31-37	TB0261X		A013	1A		D43400J		21		YN501		
0511	20	PA		64-1	27-31-37	TB0261X		A013	1A		D43400J		21		YR301-YR328		
0512	20	HL		43-1	27-31-37	D40262J			15		SM00002		9		YC051-YC052		
0512	20	PA		42-9	27-31-37	D40262J			15		SM00002		9		YC053-YL999		
0512	20	PA		33-9	27-31-37	D40262J			15		SM00002		9		YN231-YN236		
0512	20	PA		34-3	27-31-37	D43400J			15		SM00002		9		YN501		
0512	20	PA		43-6	27-31-37	D43400J			15		SM00002		9		YR301-YR328		
0513	20	HL		115-8	31-53-11	D40194P		A09			SP00054		9		YC051-YC052		
0513	20	PA		108-9	31-53-11	D40194P		A09			D40842P		12		YC053-YL999, YR301-YR328		
0513	20	PA		89-11	31-53-11	D40194P		A09			D40842P		12		YN231-YN236, YN501		
0514	20	HL		115-8	31-53-11	D40194P		B09			SP00056		9		YC051-YC052		
0514	20	PA		108-9	31-53-11	D40194P		B09			D40842P		13		YC053-YL999, YR301-YR328		
0514	20	PA		89-11	31-53-11	D40194P		B09			D40842P		13		YN231-YN236, YN501		
0515	18	PA		68-8	29-25-11	D40238P		F			D40264J		3		YC051-YC052		
0515	18	PA		68-10	29-25-11	D40238P		F			D40264J		3		YC053-YC055		
0515	18	PA		68-9	29-25-11	D40238P		F			D40264J		3		YC056-YL999, YR301-YR328		
0515	18	PA		59-3	29-25-11	D40238P		F			D40264J		3		YN231-YN236, YN501		
0516	18	PA		68-8	29-25-11	D40238P		G			D40264J		4		YC051-YC052		
0516	18	PA		68-10	29-25-11	D40238P		G			D40264J		4		YC053-YC055		
0516	18	PA		68-9	29-25-11	D40238P		G			D40264J		4		YC056-YL999, YR301-YR328		
0516	18	PA		59-3	29-25-11	D40238P		G			D40264J		4		YN231-YN236, YN501		
0517	20	PA		66-3	29-23-11	D40194P		A02			SP00504		S		YC051-YC052		
0517	20	PA		66-5	29-23-11	D40194P		A02			SP00504		S		YC053-YL999, YR301-YR328		
0517	20	PA		56-7	29-23-11	D40194P		A02			SP00504		S		YN231-YN236, YN501		
0518	20	PA		62-6	27-53-11	D40262J			8		TB0261X	A002	1A		YC051-YC052		
0518	20	PA		62-4	27-53-11	D40262J			8		TB0261X	A002	1A		YC053-YC055		
0518	20	PA		63-2	27-53-11	D40262J			8		TB0261X	A002	1A		YC056-YL999		

WIRE LIST

D280A108

91-21-11

Section W6130

Page 2

Nov 12/2012

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6134	286A6134			E/E BAY TO VERTICAL STAB (continued)											
0518	20	PA			53-6	27-53-11	D40262J		8		TB0261X	A002	1A		YN231-YN236
0518	20	PA			54-0	27-53-11	D43400J		8		TB0261X	A002	1A		YN501
0518	20	PA			63-11	27-53-11	D43400J		8		TB0261X	A002	1A		YR301-YR328
0520	20	PA			62-6	27-53-11	D40262J		9		TB0261X	B002	1A		YC051-YC052
0520	20	PA			62-4	27-53-11	D40262J		9		TB0261X	B002	1A		YC053-YC055
0520	20	PA			63-2	27-53-11	D40262J		9		TB0261X	B002	1A		YC056-YL999
0520	20	PA			53-6	27-53-11	D40262J		9		TB0261X	B002	1A		YN231-YN236
0520	20	PA			54-0	27-53-11	D43400J		9		TB0261X	B002	1A		YN501
0520	20	PA			63-11	27-53-11	D43400J		9		TB0261X	B002	1A		YR301-YR328
0521	20	PA			69-0	27-81-51	D40238P		A02		D40262J		4		YC051-YC052
0521	20	PA			69-1	27-81-51	D40238P		A02		D40262J		4		YC053-YL999
0521	20	PA			59-5	27-81-51	D40238P		A02		D40262J		4		YN231-YN236
0521	20	PA			59-11	27-81-51	D40238P		A02		D43400J		4		YN501
0521	20	PA			69-9	27-81-51	D40238P		A02		D43400J		4		YR301-YR328
0522	20	PA			69-0	27-81-51	D40238P		A03		D40262J		5		YC051-YC052
0522	20	PA			69-1	27-81-51	D40238P		A03		D40262J		5		YC053-YL999
0522	20	PA			59-5	27-81-51	D40238P		A03		D40262J		5		YN231-YN236
0522	20	PA			59-11	27-81-51	D40238P		A03		D43400J		5		YN501
0522	20	PA			69-9	27-81-51	D40238P		A03		D43400J		5		YR301-YR328
0523	20	PA			69-0	27-81-51	D40238P		B01		D40262J		6		YC051-YC052
0523	20	PA			69-1	27-81-51	D40238P		B01		D40262J		6		YC053-YL999
0523	20	PA			59-5	27-81-51	D40238P		B01		D40262J		6		YN231-YN236
0523	20	PA			59-11	27-81-51	D40238P		B01		D43400J		6		YN501
0523	20	PA			69-9	27-81-51	D40238P		B01		D43400J		6		YR301-YR328
0524	20	PA			69-0	27-81-51	D40238P		B02		D40262J		7		YC051-YC052
0524	20	PA			69-1	27-81-51	D40238P		B02		D40262J		7		YC053-YL999
0524	20	PA			59-5	27-81-51	D40238P		B02		D40262J		7		YN231-YN236
0524	20	PA			59-11	27-81-51	D40238P		B02		D43400J		7		YN501
0524	20	PA			69-9	27-81-51	D40238P		B02		D43400J		7		YR301-YR328
0525	24	PK			62-6	29-31-11	D40262J		11		TB0261X	A003	1A		YC051-YC052
0525	24	PK			62-4	29-31-11	D40262J		11		TB0261X	A003	1A		YC053-YC055
0525	24	PK			63-2	29-31-11	D40262J		11		TB0261X	A003	1A		YC056-YL999
0525	24	PK			53-6	29-31-11	D40262J		11		TB0261X	A003	1A		YN231-YN236
0525	24	PK			54-0	29-31-11	D43400J		11		TB0261X	A003	1A		YN501
0525	24	PK			63-11	29-31-11	D43400J		11		TB0261X	A003	1A		YR301-YR328
0526	22	PA			62-6	29-35-11	D40262J		10		TB0261X	B003	1A		YC051-YC052
0526	22	PA			62-4	29-35-11	D40262J		10		TB0261X	B003	1A		YC053-YC055
0526	22	PA			63-2	29-35-11	D40262J		10		TB0261X	B003	1A		YC056-YL999
0526	22	PA			53-6	29-35-11	D40262J		10		TB0261X	B003	1A		YN231-YN236

WIRE LIST

D280A108

91-21-11

Section W6130

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W6134	286A6134	E/E BAY TO VERTICAL STAB (continued)													
0526	22	PA	54-0	29-35-11	D43400J	10			TB0261X	B003	1A		YN501		
0526	22	PA	63-11	29-35-11	D43400J	10			TB0261X	B003	1A		YR301-YR328		
0527	20	PA	67-4	27-53-11	D40194P	B10			D40262J	1			YC051-YC052		
0527	20	PA	67-6	27-53-11	D40194P	B10			D40262J	1			YC053-YL999		
0527	20	PA	57-10	27-53-11	D40194P	B10			D40262J	1			YN231-YN236		
0527	20	PA	58-4	27-53-11	D40194P	B10			D43400J	1			YN501		
0527	20	PA	68-3	27-53-11	D40194P	B10			D43400J	1			YR301-YR328		
0528	20	PA	67-4	27-53-11	D40194P	B11			D40262J	2			YC051-YC052		
0528	20	PA	67-6	27-53-11	D40194P	B11			D40262J	2			YC053-YL999		
0528	20	PA	57-10	27-53-11	D40194P	B11			D40262J	2			YN231-YN236		
0528	20	PA	58-4	27-53-11	D40194P	B11			D43400J	2			YN501		
0528	20	PA	68-3	27-53-11	D40194P	B11			D43400J	2			YR301-YR328		
0529	20	PA	67-4	27-53-11	D40194P	A03			D40262J	3			YC051-YC052		
0529	20	PA	67-6	27-53-11	D40194P	A03			D40262J	3			YC053-YL999		
0529	20	PA	57-10	27-53-11	D40194P	A03			D40262J	3			YN231-YN236		
0529	20	PA	58-4	27-53-11	D40194P	A03			D43400J	3			YN501		
0529	20	PA	68-3	27-53-11	D40194P	A03			D43400J	3			YR301-YR328		
0530	18	HL	16-8	27-31-11	D40192J	7	18		SP00094		S		YC051-YC052		
0530	18	PA	16-5	27-31-11	D40192J	7	18		SP00094		S		YC053		
0530	18	PA	45-0	27-31-11	D40192J	7	18		D40264J	9			YC054-YL999,		
													YR301-YR328		
0530	18	PA	36-1	27-31-11	D40192J	7	18		D40264J	9			YN231-YN236, YN501		
0531	18	CQ	11-2	27-31-11	D40192J	24	18		SP00506		9		YC051-YC052		
0532	18	CQ	53-2	27-31-11	D40264J	5			SP00506		9		YC051-YC052		
0533	20	PA	67-1	27-31-11	D40264J	8			D40194P	B19			YC051-YC052		
0533	20	PA	67-2	27-31-11	D40264J	8			D40194P	B19			YC053-YL999,		
													YR301-YR328		
0533	20	PA	57-8	27-31-11	D40264J	8			D40194P	B19			YN231-YN236, YN501		
0534	22	PA	62-5	27-23-14	D40262J	14			TB0262X	B002	1A		YC051-YC052		
0534	22	PA	62-3	27-23-14	D40262J	14			TB0262X	B002	1A		YC053-YC055		
0534	22	PA	63-1	27-23-14	D40262J	14			TB0262X	B002	1A		YC056-YL999		
0534	22	PA	53-5	27-23-14	D40262J	14			TB0262X	B002	1A		YN231-YN236		
0534	22	PA	53-11	27-23-14	D43400J	14			TB0262X	B002	1A		YN501		
0534	22	PA	63-10	27-23-14	D43400J	14			TB0262X	B002	1A		YR301-YR328		
0535	22	GA	62-6	27-23-11	SM00006		W		TB0261X	A004	1A		YC051-YC052		
0535	22	GA	62-4	27-23-11	SM00006		W		TB0261X	A004	1A		YC053-YC055		
0535	22	GA	63-2	27-23-11	SM00006		W		TB0261X	A004	1A		YC056-YD153		
0535	22	PA	63-2	27-23-11	SM00006		W		TB0261X	A004	1A		YD154-YD155		

WIRE LIST

D280A108

91-21-11

Section W6130

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W6134	286A6134			E/E BAY TO VERTICAL STAB (continued)										
0535	22		PA	58-0	27-23-11	SM00006		9		TB0261X	A004	1A		YD157-YL999, YR301-YR328
0535	22		PA	48-6	27-23-11	SM00006		9		TB0261X	A004	1A		YN231-YN236, YN501
0536	22		PA	69-0	27-23-11	D40262J		13		D40238P	B03			YC051-YC052
0536	22		PA	69-1	27-23-11	D40262J		13		D40238P	B03			YC053-YL999
0536	22		PA	59-5	27-23-11	D40262J		13		D40238P	B03			YN231-YN236
0536	22		PA	59-11	27-23-11	D43400J		13		D40238P	B03			YN501
0536	22		PA	69-9	27-23-11	D43400J		13		D40238P	B03			YR301-YR328
0537	18		HL	32-7	27-31-11	D40264J		9		SP00092		S		YC051-YC052
0537	18		HL	32-8	27-31-11	D40264J		9		SP00092		S		YC053
0538	20		PA	67-4	27-53-12	D40262J		16		D40194P	A01			YC051-YC052
0538	20		PA	67-6	27-53-12	D40262J		16		D40194P	A01			YC053-YL999
0538	20		PA	57-10	27-53-12	D40262J		16		D40194P	A01			YN231-YN236
0538	20		PA	58-4	27-53-12	D43400J		16		D40194P	A01			YN501
0538	20		PA	68-3	27-53-12	D43400J		16		D40194P	A01			YR301-YR328
0539	20		PA	67-4	27-53-12	D40262J		17		D40194P	B01			YC051-YC052
0539	20		PA	67-6	27-53-12	D40262J		17		D40194P	B01			YC053-YL999
0539	20		PA	57-10	27-53-12	D40262J		17		D40194P	B01			YN231-YN236
0539	20		PA	58-4	27-53-12	D43400J		17		D40194P	B01			YN501
0539	20		PA	68-3	27-53-12	D43400J		17		D40194P	B01			YR301-YR328
0540	20		GA	155-0	27-23-11	D40526P		7		D43387J	10			YC051-YC052
0540	20		GA	160-0	27-23-11	D40526P		7		D40842P	20			YC053-YD153
0540	20		PA	109-2	27-23-11	D40276P		B03		D40842P	20			YD154-YL999, YR301-YR328
0540	20		PA	90-3	27-23-11	D40276P		B03		D40842P	20			YN231-YN236, YN501
0541	20		PA	110-4	27-21-11	D40238P		A07		D40842P	4			YD154-YL999, YR301-YR328
0541	20		PA	91-6	27-21-11	D40238P		A07		D40842P	4			YN231-YN236, YN501
0542	20		PA	110-4	27-21-11	D40238P		B07		D40842P	5			YD154-YL999, YR301-YR328
0542	20		PA	91-6	27-21-11	D40238P		B07		D40842P	5			YN231-YN236, YN501
0543	22		GA	30-0	27-23-11	D40262J		12		SM00006		W		YC051-YD153
0543	22		PA	30-0	27-23-11	D40262J		12		SM00006		W		YD154-YD155
0543	22		PA	6-3	27-23-11	D40262J		12		SM00006		9		YD157-YL999
0543	22		PA	5-0	27-23-11	D40262J		12		SM00006		9		YN231-YN236
0543	22		PA	6-0	27-23-11	D43400J		12		SM00006		9		YN501
0543	22		PA	6-11	27-23-11	D43400J		12		SM00006		9		YR301-YR328
0547	18		CQ	4-4	27-31-11	D40264J		5		SP00502		S		YC053-YC055
0547	18		CQ	4-7	27-31-11	D40262J		18	18	SP00502		S		YC056-YL999

WIRE LIST

D280A108

91-21-11

Section W6130

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6134	286A6134				E/E BAY TO VERTICAL STAB (continued)										
0547	18		CQ		4-9	27-31-11	D40262J	18	18		SP00502		S		YN231-YN236
0547	18		CQ		5-4	27-31-11	D43400J	18	18		SP00502		S		YN501-YR328
0548	18		CQ		46-0	27-31-11	D40192J	24	18		SP00502		S		YC053-YC055
0548	18		CQ		46-3	27-31-11	D40236J		1		SP00502		S		YC056-YL999, YR301-YR328
0548	18		CQ		37-3	27-31-11	D40236J		1		SP00502		S		YN231-YN236, YN501
0551	20		GA		56-0	27-23-11	D43387J		11		SM00006		W		YC051-YC052
0551	20		GA		56-0	27-23-11	D40842P		21		SM00006		W		YC053-YC057
0551	20		GA		52-0	27-23-11	SM00006			W	D40842P	21			YC058-YD153
0551	20		PA		46-5	27-23-11	D40842P		21		SM00006		W		YD154-YD155
0551	20		PA		47-6	27-23-11	D40842P		21		SM00006		9		YD157-YL999, YR301-YR328
0551	20		PA		37-7	27-23-11	D40842P		21		SM00006		9		YN231-YN236, YN501
0552	20		PA		46-0	27-31-37	SM00001		9		D40262J	20			YC051-YC055
0552	20		PA		42-9	27-31-37	SM00001		9		D40262J	20			YC056-YL999
0552	20		PA		33-9	27-31-37	SM00001		9		D40262J	20			YN231-YN236
0552	20		PA		34-3	27-31-37	SM00001		9		D43400J	20			YN501
0552	20		PA		43-6	27-31-37	SM00001		9		D43400J	20			YR301-YR328
1001	20		HP	AA	108-4	31-31-14	D04826J		7		D40276P	B02			YC051-YC052
1001	20		X1	AA	108-11	31-31-14	D04826J		7		D40276P	B02			YC053-YL999, YR301-YR328
1001	20		X1	AA	90-0	31-31-14	D04826J		7		D40276P	B02			YN231-YN236, YN501
1001Z				AA	0-0	31-31-14	D04826J		S/R		D40276P	PERG	1F		YC051-YN236, YN501-YR328
1101	20		N1	BN	125-0	27-25-11	D40276P		A02		D43387J	12			YC051-YC052
1101	20		N1	BN	130-0	27-25-11	D40276P		A02		D40842P	22			YC053-YD153
1101	20		X1	BN	109-2	27-25-11	D40276P		A02		D40842P	22			YD154-YL999, YR301-YR314
1101	20		X1	BN	90-3	27-25-11	D40276P		A02		D40842P	22			YN231-YN236, YN501
1101Z				BN	0-0	27-25-11	D40276P		PERG	1F	D43387J	S/R			YC051-YC052
1101Z				BN	0-0	27-25-11	D40276P		PERG	1F	D40842P	S/R			YC053-YN236, YN501-YR314
1102	20		N1	BP	125-0	27-25-11	D40276P		A03		D43387J	13			YC051-YC052
1102	20		N1	BP	130-0	27-25-11	D40276P		A03		D40842P	23			YC053-YD153
1102	20		X1	BP	109-2	27-25-11	D40276P		A03		D40842P	23			YD154-YL999, YR301-YR314
1102	20		X1	BP	90-3	27-25-11	D40276P		A03		D40842P	23			YN231-YN236, YN501
1102Z				BP	0-0	27-25-11	D40276P		PERG	1F	D43387J	S/R			YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W6130

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W6134	286A6134			E/E BAY TO VERTICAL STAB (continued)										
1102Z				BP	0-0	27-25-11	D40276P	PERG	1F		D40842P	S/R		YC053-YN236, YN501-YR314
1103	20	N1	BQ		125-0	27-25-11	D40276P	A04			D43387J	14		YC051-YC052
1103	20	N1	BQ		130-0	27-25-11	D40276P	A04			D40842P	24		YC053-YD153
1103	20	X1	BQ		109-2	27-25-11	D40276P	A04			D40842P	24		YD154-YL999, YR301-YR314
1103	20	X1	BQ		90-3	27-25-11	D40276P	A04			D40842P	24		YN231-YN236, YN501
1103Z			BQ		0-0	27-25-11	D40276P	PERG	1F		D43387J	S/R		YC051-YC052
1103Z			BQ		0-0	27-25-11	D40276P	PERG	1F		D40842P	S/R		YC053-YN236, YN501-YR314
2003B	20	HQ	GC		108-4	31-31-14	D04826J	6			D40276P	B01		YC051-YC052
2003B	20	VG	GC		108-11	31-31-14	D04826J	6			D40276P	B01		YC053-YL999, YR301-YR328
2003B	20	VG	GC		90-0	31-31-14	D04826J	6			D40276P	B01		YN231-YN236, YN501
2003R	20	HQ	GC		0-0	31-31-14	D04826J	5			D40276P	A01		YC051-YC052
2003R	20	VG	GC		0-0	31-31-14	D04826J	5			D40276P	A01		YC053-YN236, YN501-YR328
2003Z			GC		0-0	31-31-14	D04826J	S/R			D40276P	PERG	1F	YC051-YN236, YN501-YR328
2201B	20	HM	KA		108-2	27-38-11	D40194P	A10			D40192J	1		YC051-YC052
2201B	20	PB	KA		108-4	27-38-11	D40194P	A10			D40192J	1		YC053-YC055
2201B	20	PB	KA		108-5	27-38-11	D40194P	A10			D40192J	1		YC056-YL999, YR301-YR328
2201B	20	PB	KA		89-6	27-38-11	D40194P	A10			D40192J	1		YN231-YN236, YN501
2201R	20	HM	KA		0-0	27-38-11	D40194P	A11			D40192J	2		YC051-YC052
2201R	20	PB	KA		0-0	27-38-11	D40194P	A11			D40192J	2		YC053-YN236, YN501-YR328
2202B	20	HM	KB		112-2	27-28-11	D40194P	A07			D40268J	8		YC051-YC052
2202B	20	PB	KB		108-9	27-28-11	D40194P	A07			D40842P	16		YC053-YL999, YR301-YR328
2202B	20	PB	KB		89-11	27-28-11	D40194P	A07			D40842P	16		YN231-YN236, YN501
2202R	20	HM	KB		0-0	27-28-11	D40194P	A08			D40268J	9		YC051-YC052
2202R	20	PB	KB		0-0	27-28-11	D40194P	A08			D40842P	17		YC053-YN236, YN501-YR328
2203B	20	HM	KC		112-2	27-28-11	D40194P	B04			D40268J	1		YC051-YC052
2203B	20	PB	KC		108-9	27-28-11	D40194P	B04			D40842P	18		YC053-YL999, YR301-YR328
2203B	20	PB	KC		89-11	27-28-11	D40194P	B04			D40842P	18		YN231-YN236, YN501
2203R	20	HM	KC		0-0	27-28-11	D40194P	B05			D40268J	2		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W6130

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6134	286A6134			E/E BAY TO VERTICAL STAB (continued)											
2203R	20	PB	KC		0-0	27-28-11	D40194P	B05			D40842P	19			YC053-YN236, YN501-YR328
2204B	20	N2	KD		125-0	27-25-11	D40276P	A06			D43389J	11			YC051-YC052
2204B	20	N2	KD		130-0	27-25-11	D40276P	A06			D40842P	26			YC053, YC056-YD153
2204B	20	N2	KD		121-0	27-25-11	D40276P	A06			D40842P	26			YC054-YC055
2204B	20	X2	KD		109-2	27-25-11	D40276P	A06			D40842P	26			YD154-YL999, YR301-YR314
2204B	20	X2	KD		90-3	27-25-11	D40276P	A06			D40842P	26			YN231-YN236, YN501
2204R	20	N2	KD		0-0	27-25-11	D40276P	A05			D43389J	10			YC051-YC052
2204R	20	N2	KD		0-0	27-25-11	D40276P	A05			D40842P	25			YC053-YD153
2204R	20	X2	KD		0-0	27-25-11	D40276P	A05			D40842P	25			YD154-YN236, YN501-YR314
2204Z			KD		0-0	27-25-11	D40276P	PERG	1F		D43389J	S/R			YC051-YC052
2204Z			KD		0-0	27-25-11	D40276P	PERG	1F		D40842P	S/R			YC053-YN236, YN501-YR314
2205B	20	N2	KE		125-0	27-25-11	D40276P	A08			D43389J	13			YC051-YC052
2205B	20	N2	KE		130-0	27-25-11	D40276P	A08			D40842P	29			YC053-YD153
2205B	20	X2	KE		109-2	27-25-11	D40276P	A08			D40842P	29			YD154-YL999, YR301-YR314
2205B	20	X2	KE		90-3	27-25-11	D40276P	A08			D40842P	29			YN231-YN236, YN501
2205R	20	N2	KE		0-0	27-25-11	D40276P	A07			D43389J	12			YC051-YC052
2205R	20	N2	KE		0-0	27-25-11	D40276P	A07			D40842P	28			YC053-YD153
2205R	20	X2	KE		0-0	27-25-11	D40276P	A07			D40842P	28			YD154-YN236, YN501-YR314
2205Z			KE		0-0	27-25-11	D40276P	PERG	1F		D43389J	S/R			YC051-YC052
2205Z			KE		0-0	27-25-11	D40276P	PERG	1F		D40842P	S/R			YC053-YN236, YN501-YR314
2206B	20	N2	KF		125-0	27-25-11	D45203P	B02			D43389J	15			YC051-YC052
2206B	20	N2	KF		130-0	27-25-11	D45203P	B02			D40842P	31			YC053-YD153
2206B	20	X2	KF		109-2	27-25-11	D40276P	A10			D40842P	31			YD154-YL999, YR301-YR328
2206B	20	X2	KF		90-3	27-25-11	D40276P	A10			D40842P	31			YN231-YN236, YN501
2206R	20	N2	KF		0-0	27-25-11	D45203P	B03			D43389J	14			YC051-YC052
2206R	20	N2	KF		0-0	27-25-11	D45203P	B03			D40842P	30			YC053-YD153
2206R	20	X2	KF		0-0	27-25-11	D40276P	A09			D40842P	30			YD154-YN236, YN501-YR328
2206Z			KF		0-0	27-25-11	D45203P	DED			D43389J	S/R			YC051-YC052
2206Z			KF		0-0	27-25-11	D45203P	DED			D40842P	S/R			YC053-YD153

WIRE LIST

D280A108

91-21-11

Section W6130

Page 8

Nov 12/2012

Bundle No. Wire No.	Part Number			Description Fam	FT-IN	Diagram	From				To				Effectivity
	GA	CO	TY				Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W6134	286A6134			E/E BAY TO VERTICAL STAB (continued)											
2206Z				KF	0-0	27-25-11	D40276P	PERG	1F		D40842P	S/R		YD154-YN236, YN501-YR328	
2211B	20	HM	KK		108-2	27-38-11	D40194P	A12			D40192J	11		YC051-YC052	
2211B	20	PB	KK		108-4	27-38-11	D40194P	A12			D40192J	11		YC053-YC055	
2211B	20	PB	KK		108-5	27-38-11	D40194P	A12			D40192J	11		YC056-YL999, YR301-YR328	
2211B	20	PB	KK		89-6	27-38-11	D40194P	A12			D40192J	11		YN231-YN236, YN501	
2211R	20	HM	KK		0-0	27-38-11	D40194P	A13			D40192J	12		YC051-YC052	
2211R	20	PB	KK		0-0	27-38-11	D40194P	A13			D40192J	12		YC053-YN236, YN501-YR328	
2231B	20	HM	LF		108-2	27-48-11	D40194P	A14			D40192J	16		YC051-YC052	
2231B	20	PB	LF		108-4	27-48-11	D40194P	A14			D40192J	16		YC053-YC055	
2231B	20	PB	LF		108-5	27-48-11	D40194P	A14			D40192J	16		YC056-YL999, YR301-YR328	
2231B	20	PB	LF		89-6	27-48-11	D40194P	A14			D40192J	16		YN231-YN236, YN501	
2231R	20	HM	LF		0-0	27-48-11	D40194P	A15			D40192J	17		YC051-YC052	
2231R	20	PB	LF		0-0	27-48-11	D40194P	A15			D40192J	17		YC053-YN236, YN501-YR328	
3001B	20	X3	BA		67-10	31-31-14	D40276P	B08			D40262J	23		YD160-YL999	
3001B	20	X3	BA		58-2	31-31-14	D40276P	B08			D40262J	23		YN231-YN236	
3001B	20	X3	BA		58-8	31-31-14	D40276P	B08			D43400J	23		YN501	
3001B	20	X3	BA		68-7	31-31-14	D40276P	B08			D43400J	23		YR301-YR328	
3001R	20	X3	BA		0-0	31-31-14	D40276P	B07			D40262J	22		YD160-YN236	
3001R	20	X3	BA		0-0	31-31-14	D40276P	B07			D43400J	22		YN501-YR328	
3001Y	20	X3	BA		0-0	31-31-14	D40276P	B09			D40262J	24		YD160-YN236	
3001Y	20	X3	BA		0-0	31-31-14	D40276P	B09			D43400J	24		YN501-YR328	
3001Z			BA		0-0	31-31-14	D40276P	PERG	1F		D40262J	19		YD160-YN236	
3001Z			BA		0-0	31-31-14	D40276P	PERG	1F		D43400J	19		YN501-YR328	
3201B	20	HN	YA		108-2	27-38-11	D40194P	A16			D40192J	5		YC051-YC052	
3201B	20	PC	YA		108-4	27-38-11	D40194P	A16			D40192J	5		YC053-YC055	
3201B	20	PC	YA		108-5	27-38-11	D40194P	A16			D40192J	5		YC056-YL999, YR301-YR328	
3201B	20	PC	YA		89-6	27-38-11	D40194P	A16			D40192J	5		YN231-YN236, YN501	
3201R	20	HN	YA		0-0	27-38-11	D40194P	A17			D40192J	4		YC051-YC052	
3201R	20	PC	YA		0-0	27-38-11	D40194P	A17			D40192J	4		YC053-YN236, YN501-YR328	
3201Y	20	HN	YA		0-0	27-38-11	D40194P	A18			D40192J	3		YC051-YC052	
3201Y	20	PC	YA		0-0	27-38-11	D40194P	A18			D40192J	3		YC053-YN236, YN501-YR328	

WIRE LIST

D280A108

91-21-11

Section W6130

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6134	286A6134				E/E BAY TO VERTICAL STAB (continued)										
3203B	20	HN	YC		112-2	27-28-11	D40194P	B07			D40268J	5			YC051-YC052
3203B	20	PC	YC		108-9	27-28-11	D40194P	B07			D40842P	14			YC053-YL999, YR301-YR328
3203B	20	PC	YC		89-11	27-28-11	D40194P	B07			D40842P	14			YN231-YN236, YN501
3203R	20	HN	YC		0-0	27-28-11	D40194P	B06			D40268J	4			YC051-YC052
3203R	20	PC	YC		0-0	27-28-11	D40194P	B06			D40842P	15			YC053-YN236, YN501-YR328
3203Y	20	HN	YC		0-0	27-28-11	D40194P	B08			D40268J	3			YC051-YC052
3203Y	20	PC	YC		0-0	27-28-11	D40194P	B08			D40842P	27			YC053-YN236, YN501-YR328
3211B	20	HN	YK		108-2	27-38-11	D40194P	B16			D40192J	15			YC051-YC052
3211B	20	PC	YK		108-4	27-38-11	D40194P	B16			D40192J	15			YC053-YC055
3211B	20	PC	YK		108-5	27-38-11	D40194P	B16			D40192J	15			YC056-YL999, YR301-YR328
3211B	20	PC	YK		89-6	27-38-11	D40194P	B16			D40192J	15			YN231-YN236, YN501
3211R	20	HN	YK		0-0	27-38-11	D40194P	B17			D40192J	14			YC051-YC052
3211R	20	PC	YK		0-0	27-38-11	D40194P	B17			D40192J	14			YC053-YN236, YN501-YR328
3211Y	20	HN	YK		0-0	27-38-11	D40194P	B18			D40192J	13			YC051-YC052
3211Y	20	PC	YK		0-0	27-38-11	D40194P	B18			D40192J	13			YC053-YN236, YN501-YR328
3231B	20	HN	ZF		108-2	27-48-11	D40194P	B12			D40192J	20			YC051-YC052
3231B	20	PC	ZF		108-4	27-48-11	D40194P	B12			D40192J	20			YC053-YC055
3231B	20	PC	ZF		108-5	27-48-11	D40194P	B12			D40192J	20			YC056-YL999, YR301-YR328
3231B	20	PC	ZF		89-6	27-48-11	D40194P	B12			D40192J	20			YN231-YN236, YN501
3231R	20	HN	ZF		0-0	27-48-11	D40194P	B13			D40192J	19			YC051-YC052
3231R	20	PC	ZF		0-0	27-48-11	D40194P	B13			D40192J	19			YC053-YN236, YN501-YR328
3231Y	20	HN	ZF		0-0	27-48-11	D40194P	B14			D40192J	18			YC051-YC052
3231Y	20	PC	ZF		0-0	27-48-11	D40194P	B14			D40192J	18			YC053-YN236, YN501-YR328
5501	20	HL			108-0	30-31-11	D40194P	B02			D04826J	1			YC051-YC052
5501	20	PA			108-6	30-31-11	D40194P	B02			D04826J	1			YC053-YL999, YR301-YR328
5501	20	PA			89-8	30-31-11	D40194P	B02			D04826J	1			YN231-YN236, YN501
5502	20	HL			1-7	30-31-11	D04826J	4			GD01788	AC..	E		YC051-YC052
5502	20	PA			2-1	30-31-11	D04826J	4			GD01788	AC..	E		YC053-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W6130

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From		To			Effectivity				
Wire No.	GA	CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6134	286A6134			E/E BAY TO VERTICAL STAB (continued)										
5504	20	HL		108-0	30-31-12	D40194P	B03			D04826J	2			YC051-YC052
5504	20	PA		108-6	30-31-12	D40194P	B03			D04826J	2			YC053-YL999, YR301-YR328
5504	20	PA		89-8	30-31-12	D40194P	B03			D04826J	2			YN231-YN236, YN501
5505	20	HL		1-7	30-31-12	D04826J	3			GD01788	AC..	E		YC051-YC052
5505	20	PA		2-1	30-31-12	D04826J	3			GD01788	AC..	E		YC053-YN236, YN501-YR328
A-A				0-0	31-53-11	S00546	6			S00546	CAP	Y		YC051-YC052
A-B				0-0	31-53-11	S00546	5			SP00056		9		YC051-YC052
A-C				0-0	31-53-11	S00546	3			SP00054		9		YC051-YC052
A-D				0-0	31-53-11	S00546	2			S00546	CAP	Y		YC051-YC052
A-E				0-0	31-53-11	S00546	4			GD00060	DC..	1		YC051-YC052
A-F				0-0	31-53-11	S00546	1			SP00058		9		YC051-YC052
B-A				0-0	31-53-11	S00132	6			S00132	CAP	Y		YC051-YC052
B-B				0-0	31-53-11	S00132	5			SP00056		9		YC051-YC052
B-C				0-0	31-53-11	S00132	3			SP00058		9		YC051-YC052
B-D				0-0	31-53-11	S00132	2			S00132	CAP	Y		YC051-YC052
B-E				0-0	31-53-11	S00132	4			GD00060	DC..	1	*	YC051-YC052
B-F				0-0	31-53-11	S00132	1			GD00060	DC..	1	*	YC051-YC052
YAAA				0-0	27-21-11	D40268J	S/R			GD04803	ST..	E		YC051-YC052
YAAB				0-0	27-25-11	D43389J	S/R			GD04803	ST..	E		YC051-YC052
YAAC				0-0	27-25-11	D43387J	S/R			GD04803	ST..	E		YC051-YC052
W6136	286A6136			RUDDER EQUIP (VERTICAL STAB) TO DISC AB1080										
0508	20	GA		6-0	27-25-11	GD02994	ST..	E		D10197	5			YC051-YD155
0508	20	PA		10-6	27-25-11	GD02994	ST..	E		D10197	5			YD157-YD158
0508	20	PA		10-8	27-25-11	GD02994	ST..	E		D10197	5			YL951-YR328
0509	20	GA		6-0	27-25-11	GD00015	DC..	E	*	D10197	8			YC051-YC058, YC064-YC070, YD154-YD155
0509	20	GA		6-0	27-25-11	GD00015	DC..	E		D10197	8			YC059-YC063
0509	20	GA		6-0	27-25-11	GD00069	DC..	E	*	D10197	8			YD151-YD153
0509	20	PA		3-9	27-23-11	GD00069	DC..	E	*	D10197	8			YD157-YD158
0509	20	PA		3-10	27-23-11	GD00069	DC..	E	*	D10197	8			YL951-YR328
0510	20	GA		6-0	27-25-11	GD00015	DC..	E		D10197	6			YC051-YC063, YD154-YD155
0510	20	GA		6-0	27-25-11	GD00015	DC..	E	*	D10197	6			YC064-YC070
0510	20	GA		6-0	27-25-11	GD00069	DC..	E		D10197	6			YD151-YD153
0510	20	PA		3-9	27-25-11	GD00069	DC..	E	*	D10197	6			YD157-YD158

WIRE LIST

D280A108

91-21-11

Section W6130

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6136	286A6136				RUDDER EQUIP (VERTICAL STAB) TO DISC AB1080 (continued)										
0510	20		PA		3-10	27-25-11	GD00069	DC..	E	*	D10197	6			YL951-YR328
0511	20		GA		6-0	27-25-11	GD00015	DC..	E	*	D10197	7			YC051-YC058, YC064-YC070, YD154-YD155
0511	20		GA		6-0	27-25-11	GD00015	DC..	E		D10197	7			YC059-YC063
0511	20		GA		6-0	27-25-11	GD00069	DC..	E	*	D10197	7			YD151-YD153
0511	20		PA		3-9	27-25-11	GD00069	DC..	E	*	D10197	7			YD157-YD158
0511	20		PA		3-10	27-25-11	GD00069	DC..	E	*	D10197	7			YL951-YR328
1001	20		HP	AA	14-5	27-25-11	D40268P	10			D10197	15			YC051-YC063
1001	20		HP	AA	14-9	27-25-11	D40268P	10			D10197	15			YC064-YC070
1001	20		HP	AA	13-7	27-25-11	D40268P	10			D10197	15			YD151-YD155
1001	20		HP	AA	13-2	27-25-11	D40268P	10			D10197	15			YD157-YD158
1001	20		HP	AA	13-4	27-25-11	D40268P	10			D10197	15			YL951-YR328
1001Z				AA	0-0	27-25-11	D40268P	S/R			D10197	S/R			YC051-YD158, YL951-YR328
1002	20		HP	AB	14-5	27-25-11	D40268P	11			D10197	14			YC051-YC063
1002	20		HP	AB	14-9	27-25-11	D40268P	11			D10197	14			YC064-YC070
1002	20		HP	AB	13-7	27-25-11	D40268P	11			D10197	14			YD151-YD155
1002	20		HP	AB	13-2	27-25-11	D40268P	11			D10197	14			YD157-YD158
1002	20		HP	AB	13-4	27-25-11	D40268P	11			D10197	14			YL951-YR328
1002Z				AB	0-0	27-25-11	D40268P	S/R			D10197	S/R			YC051-YD158, YL951-YR328
1003	20		HP	AC	10-6	27-21-11	D40268P	13			D02932	13			YC051-YC063
1003	20		HP	AC	10-8	27-21-11	D40268P	13			D02932	13			YC064-YD155
1003	20		HP	AC	10-4	27-21-11	D40268P	13			D02932	13			YD157-YD158, YL951-YR328
1003Z				AC	0-0	27-21-11	D40268P	S/R			D02932	S/R			YC051-YD158, YL951-YR328
1004	20		HP	AD	10-6	27-21-11	D40268P	12			D02932	2			YC051-YC063
1004	20		HP	AD	10-8	27-21-11	D40268P	12			D02932	2			YC064-YD155
1004	20		HP	AD	10-4	27-21-11	D40268P	12			D02932	2			YD157-YD158, YL951-YR328
1004Z				AD	0-0	27-21-11	D40268P	S/R			D02932	S/R			YC051-YD158, YL951-YR328
1005	20		HP	AE	10-6	27-21-11	D40268P	14			D02932	3			YC051-YC063
1005	20		HP	AE	10-8	27-21-11	D40268P	14			D02932	3			YC064-YD155
1005	20		HP	AE	10-4	27-21-11	D40268P	14			D02932	3			YD157-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W6130

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6136	286A6136			RUDDER EQUIP (VERTICAL STAB) TO DISC AB1080 (continued)											
1005Z				AE	0-0	27-21-11	D40268P	S/R			D02932	S/R			YC051-YD158, YL951-YR328
1006	20	HP	AF		10-6	27-28-11	D40268P	6			D02932	6			YC051-YC063
1006	20	HP	AF		10-8	27-28-11	D40268P	6			D02932	6			YC064-YD155
1006	20	HP	AF		10-4	27-28-11	D40268P	6			D02932	6			YD157-YD158, YL951-YR328
1006Z				AF	0-0	27-28-11	D40268P	S/R			D02932	S/R			YC051-YD158, YL951-YR328
1007	20	HP	AG		10-6	27-28-11	D40268P	7			D02932	7			YC051-YC063
1007	20	HP	AG		10-8	27-28-11	D40268P	7			D02932	7			YC064-YD155
1007	20	HP	AG		10-4	27-28-11	D40268P	7			D02932	7			YD157-YD158, YL951-YR328
1007Z				AG	0-0	27-28-11	D40268P	S/R			D02932	S/R			YC051-YD158, YL951-YR328
1008	20	HP	AH		3-4	27-21-11	D02932	15			GD02994	ST..	E	*	YC051-YC063
1008	20	HP	AH		3-11	27-21-11	D02932	15			GD02994	ST..	E	*	YC064-YC070
1008	20	HP	AH		2-9	27-21-11	D02932	15			GD02994	ST..	E	*	YD151-YD158
1008	20	HP	AH		2-10	27-21-11	D02932	15			GD02994	ST..	E	*	YL951-YR328
1008Z				AH	0-0	27-21-11	D02932	S/R			GD02994	ST..	E	*	YC051-YD158, YL951-YR328
1009	20	GE	AI		14-0	27-25-11	D43387P	11			D10197	2			YC051-YC052
1009	20	GE	AI		14-0	27-25-11	D40268P	18			D10197	2			YC053-YD155
1009	20	VF	AI		13-2	27-23-11	D40268P	18			D10197	2			YD157-YD158
1009	20	VF	AI		13-4	27-23-11	D40268P	18			D10197	2			YL951-YR328
1009Z				AI	0-0	27-25-11	D43387P	S/R			D10197	S/R			YC051-YC052
1009Z				AI	0-0	27-25-11	D40268P	S/R			D10197	S/R			YC053-YD155
1009Z				AI	0-0	27-23-11	D40268P	S/R			D10197	S/R			YD157-YD158, YL951-YR328
1010	20	GE	AJ		14-0	27-25-11	D43387P	10			D10197	1			YC051-YC052
1010	20	GE	AJ		14-0	27-25-11	D40268P	19			D10197	1			YC053-YD155
1010	20	VF	AJ		13-2	27-23-11	D40268P	19			D10197	1			YD157-YD158
1010	20	VF	AJ		13-4	27-23-11	D40268P	19			D10197	1			YL951-YR328
1010Z				AJ	0-0	27-25-11	D43387P	S/R			D10197	S/R			YC051-YC052
1010Z				AJ	0-0	27-25-11	D40268P	S/R			D10197	S/R			YC053-YD155
1010Z				AJ	0-0	27-23-11	D40268P	S/R			D10197	S/R			YD157-YD158, YL951-YR328
2002B	20	GF	GB		14-0	27-25-11	D43389P	15			D10197	4			YC051-YC052
2002B	20	GF	GB		14-0	27-25-11	D40268P	17			D10197	4			YC053-YD155
2002B	20	VG	GB		13-2	27-25-11	D40268P	17			D10197	4			YD157-YD158

WIRE LIST

D280A108

91-21-11

Section W6130

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6136	286A6136			RUDDER EQUIP (VERTICAL STAB) TO DISC AB1080 (continued)											
2002B	20	VG	GB		13-4	27-25-11	D40268P		17		D10197		4		YL951-YR328
2002R	20	GF	GB		0-0	27-25-11	D43389P		14		D10197		3		YC051-YC052
2002R	20	GF	GB		0-0	27-25-11	D40268P		16		D10197		3		YC053-YD155
2002R	20	VG	GB		0-0	27-25-11	D40268P		16		D10197		3		YD157-YD158, YL951-YR328
2002Z			GB		0-0	27-25-11	D43389P		S/R		D10197		S/R		YC051-YC052
2002Z			GB		0-0	27-25-11	D40268P		S/R		D10197		S/R		YC053-YD158, YL951-YR328
2202B	20	HQ	KB		10-6	27-28-11	D40268P		8		D02932		4		YC051-YC063
2202B	20	HQ	KB		10-8	27-28-11	D40268P		8		D02932		4		YC064-YD155
2202B	20	HQ	KB		10-4	27-28-11	D40268P		8		D02932		4		YD157-YD158, YL951-YR328
2202R	20	HQ	KB		0-0	27-28-11	D40268P		9		D02932		5		YC051-YD158, YL951-YR328
2202Z			KB		0-0	27-28-11	D40268P		S/R		D02932		S/R		YC051-YD158, YL951-YR328
2203B	20	HQ	KC		16-1	27-28-11	D40268P		1		D03576		1		YC051-YC063
2203B	20	HQ	KC		16-11	27-28-11	D40268P		1		D03576		1		YC064-YC070
2203B	20	HQ	KC		15-7	27-28-11	D40268P		1		D03576		1		YD151-YD155
2203B	20	HQ	KC		15-5	27-28-11	D40268P		1		D03576		1		YD157-YD158
2203B	20	HQ	KC		15-6	27-28-11	D40268P		1		D03576		1		YL951-YR328
2203R	20	HQ	KC		0-0	27-28-11	D40268P		2		D03576		2		YC051-YD158, YL951-YR328
2203Z			KC		0-0	27-28-11	D40268P		S/R		D03576		S/R		YC051-YD158, YL951-YR328
3203B	20	HR	YC		16-1	27-28-11	D40268P		5		D03576		5		YC051-YC063
3203B	20	HR	YC		16-11	27-28-11	D40268P		5		D03576		5		YC064-YC070
3203B	20	HR	YC		15-7	27-28-11	D40268P		5		D03576		5		YD151-YD155
3203B	20	HR	YC		15-5	27-28-11	D40268P		5		D03576		5		YD157-YD158
3203B	20	HR	YC		15-6	27-28-11	D40268P		5		D03576		5		YL951-YR328
3203R	20	HR	YC		0-0	27-28-11	D40268P		4		D03576		4		YC051-YD158, YL951-YR328
3203Y	20	HR	YC		0-0	27-28-11	D40268P		3		D03576		3		YC051-YD158, YL951-YR328
3203Z			YC		0-0	27-28-11	D40268P		S/R		D03576		S/R		YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11
Section W6130
Page 14 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6162	286A6162			RIGHT WING BODY PRESS SEAL TO E/E BAY											
0001	20		PA		3-5	31-35-05	D39922		1		GD00072	ST..	1		YL963-YL999, YR301-YR328
0001	20		PA		3-1	31-35-05	D39922		1		GD00072	ST..	1		YN236-YN501
0007	20		PA		3-3	36-11-11	D39922		2		GD00072	DC..	1		YC055
0007	20		PA		3-5	36-11-11	D39922		2		GD00072	DC..	1		YC056-YL999, YR301-YR328
0007	20		PA		3-1	36-11-11	D39922		2		GD00072	DC..	1		YN231-YN501
0008	20		PA		3-3	73-21-12	D39922		9		GD00072	DC..	1		YC055
0008	20		PA		3-5	73-21-12	D39922		9		GD00072	DC..	1		YC056-YL999, YR301-YR328
0008	20		PA		3-1	73-21-12	D39922		9		GD00072	DC..	1		YN231-YN501
0009	20		PA		3-3	78-35-21	D39922		13		GD00072	DC..	1		YC055
0009	20		PA		3-5	78-35-21	D39922		13		GD00072	DC..	1		YC056-YL999, YR301-YR328
0009	20		PA		3-1	78-35-21	D39922		13		GD00072	DC..	1		YN231-YN501
0010	20		PA		3-3	30-11-11	D39922		16		GD00072	DC..	1		YC055
0010	20		PA		3-5	30-11-11	D39922		16		GD00072	DC..	1		YC056-YL999, YR301-YR328
0010	20		PA		3-1	30-11-11	D39922		16		GD00072	DC..	1		YN231-YN501
0011	20		PA		3-3	78-36-21	D39922		17		GD00072	DC..	1		YC055
0011	20		PA		3-5	78-36-21	D39922		17		GD00072	DC..	1		YC056-YL999, YR301-YR328
0011	20		PA		3-1	78-36-21	D39922		17		GD00072	DC..	1		YN231-YN501
0012	20		PA		3-3	36-11-11	D39922		29		GD00072	DC..	1		YC055
0012	20		PA		3-5	36-11-11	D39922		29		GD00072	DC..	1		YC056-YL999, YR301-YR328
0012	20		PA		3-1	36-11-11	D39922		29		GD00072	DC..	1		YN231-YN501
0013	20		PA		3-3	78-36-21	D39922		39		GD00072	DC..	1		YC055
0013	20		PA		3-5	78-36-21	D39922		39		GD00072	DC..	1		YC056-YL999, YR301-YR328
0013	20		PA		3-1	78-36-21	D39922		39		GD00072	DC..	1		YN231-YN501
1301	24	Y1	EN		49-3	73-21-12	D39922		21		TB0606Y	B005	1A		YC054, YC056-YL999, YR301-YR328
1301	24	Y1	EN		49-1	73-21-12	D39922		21		TB0606Y	B005	1A		YC055
1301	24	Y1	EN		39-4	73-21-12	D39922		21		TB0606Y	B005	1A		YN231-YN501
1301Z			EN		0-0	73-21-12	D39922		S/R		GB00606	ST..	1A		YC054-YR328
2001B	20	X2	AA		32-6	31-35-05	D39922		32		D40156P	B16			YL963-YL999, YR301-YR328
2001B	20	X2	AA		22-7	31-35-05	D39922		32		D40156P	B16			YN236-YN501

WIRE LIST

D280A108

91-21-11

Section W6160

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6162	286A6162				RIGHT WING BODY PRESS SEAL TO E/E BAY (continued)										
2001R	20	X2	AA		0-0	31-35-05	D39922		33		D40156P	A16			YL963-YL999, YN236-YR328
2001Z			AA		0-0	31-35-05	D39922		S/R		D40156P	PERG	1F		YL963-YL999, YN236-YR328
2601B	22	VX	SA		32-8	77-31-21	D39922		8		D40156P	A04			YC054
2601B	22	VX	SA		32-3	77-31-21	D39922		8		D40156P	A04			YC055
2601B	22	VX	SA		32-6	77-31-21	D39922		8		D40156P	A04			YC056-YL999, YR301-YR328
2601B	22	VX	SA		22-7	77-31-21	D39922		8		D40156P	A04			YN231-YN501
2601W	22	VX	SA		0-0	77-31-21	D39922		18		D40156P	B04			YC054-YR328
2601Z			SA		0-0	77-31-21	D39922		39		D40156P	A05			YC054
2601Z			SA		0-0	77-31-21	D39922		7		D40156P	A05			YC055-YR328
2602B	24	Y2	SB		32-8	73-24-21	D39922		34		D40156P	A06			YC054
2602B	24	Y2	SB		32-3	73-24-21	D39922		34		D40156P	A06			YC055
2602B	24	Y2	SB		32-6	73-24-21	D39922		34		D40156P	A06			YC056-YL999, YR301-YR328
2602B	24	Y2	SB		22-7	73-24-21	D39922		34		D40156P	A06			YN231-YN501
2602R	24	Y2	SB		0-0	73-24-21	D39922		15		D40156P	B06			YC054-YR328
2602Z			SB		0-0	73-24-21	D39922		S/R		D40156P	PERG	1F		YC054-YR328
2603B	24	Y2	SC		32-8	73-24-12	D39922		35		D40156P	A07			YC054
2603B	24	Y2	SC		32-3	73-24-12	D39922		35		D40156P	A07			YC055
2603B	24	Y2	SC		32-6	73-24-12	D39922		35		D40156P	A07			YC056-YL999, YR301-YR328
2603B	24	Y2	SC		22-7	73-24-12	D39922		35		D40156P	A07			YN231-YN501
2603R	24	Y2	SC		0-0	73-24-12	D39922		36		D40156P	B07			YC054-YR328
2603Z			SC		0-0	73-24-12	D39922		S/R		D40156P	PERG	1F		YC054-YR328
2604B	22	PB	SD		32-8	78-36-21	D39922		19		D40156P	A08			YC054
2604B	22	PB	SD		32-3	78-36-21	D39922		19		D40156P	A08			YC055
2604B	22	PB	SD		32-6	78-36-21	D39922		19		D40156P	A08			YC056-YL999, YR301-YR328
2604B	22	PB	SD		22-7	78-36-21	D39922		19		D40156P	A08			YN231-YN501
2604R	22	PB	SD		0-0	78-36-21	D39922		20		D40156P	B08			YC054-YR328
2606B	24	Y2	SF		32-8	73-21-11	D39922		23		D40156P	A09			YC054
2606B	24	Y2	SF		32-3	73-21-11	D39922		23		D40156P	A09			YC055
2606B	24	Y2	SF		32-6	73-21-11	D39922		23		D40156P	A09			YC056-YL999, YR301-YR328
2606B	24	Y2	SF		22-7	73-21-11	D39922		23		D40156P	A09			YN231-YN501
2606R	24	Y2	SF		0-0	73-21-11	D39922		22		D40156P	B09			YC054-YR328
2606Z			SF		0-0	73-21-11	D39922		S/R		D40156P	PERG	1F		YC054-YR328

WIRE LIST

D280A108

91-21-11

Section W6160

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W6162	286A6162				RIGHT WING BODY PRESS SEAL TO E/E BAY (continued)										
2607B	20	X2	SG		53-4	73-21-21	D39922		27			D11164	5		YC054
2607B	20	X2	SG		53-2	73-21-21	D39922		27			D11164	5		YC055
2607B	20	X2	SG		53-5	73-21-21	D39922		27			D11164	5		YC056-YL999, YR301-YR328
2607B	20	X2	SG		43-0	73-21-21	D39922		27			D11164	5		YN231-YN501
2607R	20	X2	SG		0-0	73-21-21	D39922		28			D11164	15		YC054-YR328
2607Z			SG		0-0	73-21-21	D39922		S/R			D11164	S/R		YC054-YR328
2608B	20	X2	SH		53-4	73-21-21	D39922		25			D11164	2		YC054
2608B	20	X2	SH		53-2	73-21-21	D39922		25			D11164	2		YC055
2608B	20	X2	SH		53-5	73-21-21	D39922		25			D11164	2		YC056-YL999, YR301-YR328
2608B	20	X2	SH		43-0	73-21-21	D39922		25			D11164	2		YN231-YN501
2608R	20	X2	SH		0-0	73-21-21	D39922		24			D11164	10		YC054-YR328
2608Z			SH		0-0	73-21-21	D39922		S/R			D11164	S/R		YC054-YR328
2609B	20	X2	SI		53-4	73-21-21	D39922		11			D11164	7		YC054
2609B	20	X2	SI		53-2	73-21-21	D39922		11			D11164	7		YC055
2609B	20	X2	SI		53-5	73-21-21	D39922		11			D11164	7		YC056-YL999, YR301-YR328
2609B	20	X2	SI		43-0	73-21-21	D39922		11			D11164	7		YN231-YN501
2609R	20	X2	SI		0-0	73-21-21	D39922		26			D11164	8		YC054-YR328
2609Z			SI		0-0	73-21-21	D39922		S/R			D11164	S/R		YC054-YR328
2610B	22	PB	SJ		32-8	78-36-21	D39922		38			D40156P	A13		YC054
2610B	22	PB	SJ		32-3	78-36-21	D39922		38			D40156P	A13		YC055
2610B	22	PB	SJ		32-6	78-36-21	D39922		38			D40156P	A13		YC056-YL999, YR301-YR328
2610B	22	PB	SJ		22-7	78-36-21	D39922		38			D40156P	A13		YN231-YN501
2610R	22	PB	SJ		0-0	78-36-21	D39922		37			D40156P	B13		YC054-YR328
2611B	20	PB	SK		32-8	SPARE	D39922		14			D40156P	A14		YC054
2611B	20	PB	SK		32-3	SPARE	D39922		14			D40156P	A14		YC055
2611B	20	PB	SK		32-6	SPARE	D39922		14			D40156P	A14		YC056-YL999, YR301-YR328
2611B	20	PB	SK		22-7	SPARE	D39922		14			D40156P	A14		YN231-YN501
2611R	20	PB	SK		0-0	SPARE	D39922		5			D40156P	B14		YC054-YR328
2612B	20	PB	SL		32-8	SPARE	D39922		31			D40156P	A15		YC054
2612B	20	PB	SL		32-3	SPARE	D39922		31			D40156P	A15		YC055
2612B	20	PB	SL		32-6	SPARE	D39922		31			D40156P	A15		YC056-YL999, YR301-YR328
2612B	20	PB	SL		22-7	SPARE	D39922		31			D40156P	A15		YN231-YN501
2612R	20	PB	SL		0-0	SPARE	D39922		30			D40156P	B15		YC054-YR328

WIRE LIST

D280A108

91-21-11

Section W6160

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W6162	286A6162				RIGHT WING BODY PRESS SEAL TO E/E BAY (continued)											
5501	24		PK		32-8	36-11-11		D39922		10		D40156P		B01		YC054
5501	24		PK		32-3	36-11-11		D39922		10		D40156P		B01		YC055
5501	24		PK		32-6	36-11-11		D39922		10		D40156P		B01		YC056-YL999, YR301-YR328
5501	24		PK		22-7	36-11-11		D39922		10		D40156P		B01		YN231-YN501
5502	24		PK		32-8	36-11-11		D39922		3		D40156P		A02		YC054
5502	24		PK		32-3	36-11-11		D39922		3		D40156P		A02		YC055
5502	24		PK		32-6	36-11-11		D39922		3		D40156P		A02		YC056-YL999, YR301-YR328
5502	24		PK		22-7	36-11-11		D39922		3		D40156P		A02		YN231-YN501
5503	24		PK		32-8	36-11-11		D39922		12		D40156P		B02		YC054
5503	24		PK		32-3	36-11-11		D39922		12		D40156P		B02		YC055
5503	24		PK		32-6	36-11-11		D39922		12		D40156P		B02		YC056-YL999, YR301-YR328
5503	24		PK		22-7	36-11-11		D39922		12		D40156P		B02		YN231-YN501
6001	22		CQ		49-3	30-11-11		D39922		6		TB0606X		A004	1A	YC054, YC056-YL999, YR301-YR328
6001	22		CQ		49-1	30-11-11		D39922		6		TB0606X		A004	1A	YC055
6001	22		CQ		39-4	30-11-11		D39922		6		TB0606X		A004	1A	YN231-YN501
6002	20		PA		49-3	78-35-21		D39922		4		TB0606Y		A007	1A	YC054, YC056-YL999, YR301-YR328
6002	20		PA		49-1	78-35-21		D39922		4		TB0606Y		A007	1A	YC055
6002	20		PA		39-4	78-35-21		D39922		4		TB0606Y		A007	1A	YN231-YN501
6003	20		PA		3-8	73-21-21		D11164		13		GD00815		ST..	1A	YC054-YR328
W6164	286A6164				RIGHT WING BODY PRESS SEAL TO E/E BAY											
0501	22		CQ		43-11	29-11-11		D39934		30		D40140P		A01		YC051-YC055
0501	22		CQ		44-0	29-11-11		D39934		30		D40140P		A01		YC056-YD153
0501	22		CQ		44-0	29-11-11		D39934		18		D40140P		A01		YD154-YL999, YR301-YR328
0501	22		CQ		34-5	29-11-11		D39934		18		D40140P		A01		YN231-YN236, YN501
1101	18		X1	BN	43-10	24-11-21		D39934		10		D40720P		K		YC051-YC055
1101	18		X1	BN	43-11	24-11-21		D39934		10		D40720P		K		YC056-YL999, YR301-YR328
1101	18		X1	BN	34-5	24-11-21		D39934		10		D40720P		K		YN231-YN236, YN501
1101Z				BN	0-0	24-11-21		D39934		S/R		D40720P		PERG	1F	YC051-YN236, YN501-YR328
1301	20		X1	EN	39-5	28-21-11		SP00318			S	D40140P		A08		YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W6160

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W6164	286A6164			RIGHT WING BODY PRESS SEAL TO E/E BAY (continued)										
1301	20	X1	EN	39-6	28-21-11	SP00318		S		D40140P	A08		YC056-YL999, YR301-YR328	
1301	20	X1	EN	28-4	28-21-11	SP00318		S		D40140P	A08		YN231-YN236, YN501	
1301Z			EN	0-0	28-21-11	SP00318	DED			D40140P	PERG	1F	YC051-YN236, YN501-YR328	
2201B	20	X2	KA	43-10	24-21-21	D39934		38		D40720P	F		YC051-YC055	
2201B	20	X2	KA	43-11	24-21-21	D39934		38		D40720P	F		YC056-YL999, YR301-YR328	
2201B	20	X2	KA	34-5	24-21-21	D39934		38		D40720P	F		YN231-YN236, YN501	
2201R	20	X2	KA	0-0	24-21-21	D39934		37		D40720P	G		YC051-YN236, YN501-YR328	
2201Z			KA	0-0	24-21-21	D39934		36		D40720P	A10		YC051-YN236, YN501-YR328	
2202B	22	PB	KB	43-10	24-11-21	D39934		39		D40720P	A02		YC051-YC055	
2202B	22	PB	KB	43-11	24-11-21	D39934		39		D40720P	A02		YC056-YL999, YR301-YR328	
2202B	22	PB	KB	34-5	24-11-21	D39934		39		D40720P	A02		YN231-YN236, YN501	
2202R	22	PB	KB	0-0	24-11-21	D39934		19		D40720P	B02		YC051-YN236, YN501-YR328	
2602B	20	PB	SB	43-10	SPARE	D39934		26		D40720P	A09		YC051-YC055	
2602B	20	PB	SB	43-11	SPARE	D39934		26		D40720P	A09		YC056-YL999, YR301-YR328	
2602B	20	PB	SB	34-5	SPARE	D39934		26		D40720P	A09		YN231-YN236, YN501	
2602R	20	PB	SB	0-0	SPARE	D39934		25		D40720P	B09		YC051-YN236, YN501-YR328	
3201B	18	X3	YA	43-11	24-21-21	D39934		17		D40140P	G		YC051-YC055	
3201B	18	X3	YA	44-0	24-21-21	D39934		17		D40140P	G		YC056-YD153	
3201B	18	X3	YA	44-0	24-21-21	D39934		12		D40140P	G		YD154-YL999, YR301-YR328	
3201B	18	X3	YA	34-5	24-21-21	D39934		12		D40140P	G		YN231-YN236, YN501	
3201R	18	X3	YA	0-0	24-21-21	D39934		6		D40140P	H		YC051-YD153	
3201R	18	X3	YA	0-0	24-21-21	D39934		1		D40140P	H		YD154-YN236, YN501-YR328	
3201Y	18	X3	YA	0-0	24-21-21	D39934		16		D40140P	J		YC051-YD153	
3201Y	18	X3	YA	0-0	24-21-21	D39934		14		D40140P	J		YD154-YN236, YN501-YR328	
3201Z			YA	0-0	24-21-21	D39934		5		D40140P	A10		YC051-YN236, YN501-YR328	
4101B	20	X4	N6	43-11	24-24-21	D39934		33		D40140P	A03		YC051-YC055	

WIRE LIST

D280A108

91-21-11

Section W6160

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity			
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type	Splice	
W6164	286A6164				RIGHT WING BODY PRESS SEAL TO E/E BAY (continued)												
4101B	20	X4	N6		44-0	24-24-21		D39934		33		D40140P	A03			YC056-YD153	
4101B	20	X4	N6		44-0	24-24-21		D39934		15		D40140P	A03			YD154-YL999, YR301-YR328	
4101B	20	X4	N6		34-5	24-24-21		D39934		15		D40140P	A03			YN231-YN236, YN501	
4101G	20	X4	N6		0-0	24-24-21		D39934		15		D40140P	B03			YC051-YD153	
4101G	20	X4	N6		0-0	24-24-21		D39934		33		D40140P	B03			YD154-YN236, YN501-YR328	
4101R	20	X4	N6		0-0	24-24-21		D39934		34		D40140P	A04			YC051-YD153	
4101R	20	X4	N6		0-0	24-24-21		D39934		35		D40140P	A04			YD154-YN236, YN501-YR328	
4101Y	20	X4	N6		0-0	24-24-21		D39934		35		D40140P	B04			YC051-YD153	
4101Y	20	X4	N6		0-0	24-24-21		D39934		32		D40140P	B04			YD154-YN236, YN501-YR328	
4101Z			N6		0-0	24-24-21		D39934		S/R		D40140P	PERG	1F		YC051-YN236, YN501-YR328	
W6166	286A6166				RIGHT WING BODY PRESS SEAL TO E/E BAY												
2202B	24	PL	KB		48-0	27-81-22		D39902		19		D40142P	A01			YC051-YC055	
2202B	24	PL	KB		48-7	27-81-22		D39902		19		D40142P	A01			YC056-YL999, YR301-YR328	
2202B	24	PL	KB		38-3	27-81-22		D39902		19		D40142P	A01			YN231-YN501	
2202R	24	PL	KB		0-0	27-81-22		D39902		8		D40142P	B01			ALL	
2204B	24	PL	KD		48-0	27-81-22		D39902		18		D40142P	A02			YC051-YC055	
2204B	24	PL	KD		48-7	27-81-22		D39902		18		D40142P	A02			YC056-YL999, YR301-YR328	
2204B	24	PL	KD		38-3	27-81-22		D39902		18		D40142P	A02			YN231-YN501	
2204R	24	PL	KD		0-0	27-81-22		D39902		39		D40142P	B02			ALL	
2205B	24	PL	KE		48-0	27-81-22		D39902		21		D40142P	A03			YC051-YC055	
2205B	24	PL	KE		48-7	27-81-22		D39902		21		D40142P	A03			YC056-YL999, YR301-YR328	
2205B	24	PL	KE		38-3	27-81-22		D39902		21		D40142P	A03			YN231-YN501	
2205R	24	PL	KE		0-0	27-81-22		D39902		20		D40142P	B03			ALL	
2206B	24	PL	KF		48-0	27-81-22		D39902		23		D40142P	A04			YC051-YC055	
2206B	24	PL	KF		48-7	27-81-22		D39902		23		D40142P	A04			YC056-YL999, YR301-YR328	
2206B	24	PL	KF		38-3	27-81-22		D39902		23		D40142P	A04			YN231-YN501	
2206R	24	PL	KF		0-0	27-81-22		D39902		22		D40142P	B04			ALL	
2207B	24	PL	KG		48-0	27-81-22		D39902		25		D40142P	A05			YC051-YC055	

WIRE LIST

D280A108

91-21-11

Section W6160

Page 6

Nov 12/2012

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6166	286A6166			RIGHT WING BODY PRESS SEAL TO E/E BAY (continued)											
2207B	24	PL	KG		48-7	27-81-22	D39902		25		D40142P	A05			YC056-YL999, YR301-YR328
2207B	24	PL	KG		38-3	27-81-22	D39902		25		D40142P	A05			YN231-YN501
2207R	24	PL	KG		0-0	27-81-22	D39902		24		D40142P	B05			ALL
2208B	24	PL	KH		48-0	27-81-22	D39902		28		D40142P	A06			YC051-YC055
2208B	24	PL	KH		48-7	27-81-22	D39902		28		D40142P	A06			YC056-YL999, YR301-YR328
2208B	24	PL	KH		38-3	27-81-22	D39902		28		D40142P	A06			YN231-YN501
2208R	24	PL	KH		0-0	27-81-22	D39902		27		D40142P	B06			ALL
2211B	24	PL	KK		48-0	27-81-22	D39902		36		D40142P	A07			YC051-YC055
2211B	24	PL	KK		48-7	27-81-22	D39902		36		D40142P	A07			YC056-YL999, YR301-YR328
2211B	24	PL	KK		38-3	27-81-22	D39902		36		D40142P	A07			YN231-YN501
2211R	24	PL	KK		0-0	27-81-22	D39902		35		D40142P	B07			ALL
2212B	24	PL	KL		48-0	27-81-22	D39902		38		D40142P	A08			YC051-YC055
2212B	24	PL	KL		48-7	27-81-22	D39902		38		D40142P	A08			YC056-YL999, YR301-YR328
2212B	24	PL	KL		38-3	27-81-22	D39902		38		D40142P	A08			YN231-YN501
2212R	24	PL	KL		0-0	27-81-22	D39902		37		D40142P	B08			ALL
2213B	24	PL	KM		48-0	27-81-22	D39902		12		D40948P	B01			YC051-YC055
2213B	24	PL	KM		48-7	27-81-22	D39902		12		D40948P	B01			YC056-YL999, YR301-YR328
2213B	24	PL	KM		38-3	27-81-22	D39902		12		D40948P	B01			YN231-YN501
2213R	24	PL	KM		0-0	27-81-22	D39902		11		D40948P	A01			ALL
2214B	24	PL	KN		48-0	27-81-22	D39902		16		D40948P	B02			YC051-YC055
2214B	24	PL	KN		48-7	27-81-22	D39902		16		D40948P	B02			YC056-YL999, YR301-YR328
2214B	24	PL	KN		38-3	27-81-22	D39902		16		D40948P	B02			YN231-YN501
2214R	24	PL	KN		0-0	27-81-22	D39902		15		D40948P	A02			ALL
2215B	24	PL	KP		48-0	27-81-22	D39902		30		D40948P	B03			YC051-YC055
2215B	24	PL	KP		48-7	27-81-22	D39902		30		D40948P	B03			YC056-YL999, YR301-YR328
2215B	24	PL	KP		38-3	27-81-22	D39902		30		D40948P	B03			YN231-YN501
2215R	24	PL	KP		0-0	27-81-22	D39902		29		D40948P	A03			ALL
6004R	20	PH			48-0	26-12-11	D39902		14		D40142P	A10			YC051-YC055
6004R	20	PH			48-7	26-12-11	D39902		14		D40142P	A10			YC056-YD153
6004R	20	PH			48-7	26-12-11	D39902		1		D40142P	A10			YD154-YL999, YR301-YR328
6004R	20	PH			38-3	26-12-11	D39902		1		D40142P	A10			YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W6160

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W6166	286A6166				RIGHT WING BODY PRESS SEAL TO E/E BAY (continued)											
6005	22		PA		48-0	30-11-11		D39902				D40142P	B10			YC051-YC055
6005	22		PA		48-7	30-11-11		D39902				D40142P	B10			YC056-YD153
6005	22		PA		48-7	30-11-11		D39902				D40142P	B10			YD154-YL999, YR301-YR328 YN231-YN501
6005	22		PA		38-3	30-11-11		D39902				D40142P	B10			
W6168	286A6168				RIGHT WING BODY PRESS SEAL TO E/E BAY											
1301	20	X1	EN		32-5	73-22-11		D39930				D40144P	A06			YC051-YC055
1301	20	X1	EN		32-3	73-22-11		D39930				D40144P	A06			YC056-YL999, YR301-YR328 YN231-YN501
1301	20	X1	EN		22-3	73-22-11		D39930				D40144P	A06			YN231-YN501
1301Z			EN		0-0	73-22-11		D39930		S/R		D40144P	PERG	1F		ALL
1302	20	X1	EP		32-5	74-11-11		D39930				D40144P	A04			YC051-YC055
1302	20	X1	EP		32-3	74-11-11		D39930				D40144P	A04			YC056-YD153
1302	20	X1	EP		32-3	74-11-11		D39930				D40144P	A04			YD154-YL999, YR301-YR328 YN231-YN501
1302	20	X1	EP		22-3	74-11-11		D39930				D40144P	A04			YN231-YN501
1302Z			EP		0-0	74-11-11		D39930		S/R		D40144P	PERG	1F		ALL
2601B	20	VG	SA		32-5	SPARE		D39930				D40144P	A01			YC051-YC055
2601B	20	VG	SA		32-3	SPARE		D39930				D40144P	A01			YC056-YL999, YR301-YR328 YN231-YN501
2601B	20	VG	SA		22-3	SPARE		D39930				D40144P	A01			ALL
2601R	20	VG	SA		0-0	SPARE		D39930				D40144P	B01			ALL
2601Z			SA		0-0	SPARE		D39930		S/R		D40144P	PERG	1F		ALL
2602B	20	VG	SB		32-5	SPARE		D39930				D40144P	A02			YC051-YC055
2602B	20	VG	SB		32-3	SPARE		D39930				D40144P	A02			YC056-YL999, YR301-YR328 YN231-YN501
2602B	20	VG	SB		22-3	SPARE		D39930				D40144P	A02			ALL
2602R	20	VG	SB		0-0	SPARE		D39930				D40144P	B02			ALL
2602Z			SB		0-0	SPARE		D39930		S/R		D40144P	PERG	1F		ALL
6004R	20	PH			32-5	26-11-21		D39930				D40144P	A03			YC051-YC055
6004R	20	PH			32-3	26-11-21		D39930				D40144P	A03			YC056-YL999, YR301-YR328 YN231-YN501
6004R	20	PH			22-3	26-11-21		D39930				D40144P	A03			ALL
6005R	20	PH			32-5	26-11-21		D39930				D40144P	B03			YC051-YC055
6005R	20	PH			32-3	26-11-21		D39930				D40144P	B03			YC056-YL999, YR301-YR328 YN231-YN501
6005R	20	PH			22-3	26-11-21		D39930				D40144P	B03			ALL

WIRE LIST

D280A108

91-21-11

Section W6160

Page 8 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Description		From			To			Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type
W6170	286A6170			RIGHT WING BODY PRESS SEAL TO E/E BAY										
1302	20	X1	EP	71-9	73-22-11	D39926		5		D46144P	A06		YC051-YC052	
1302	20	X1	EP	71-7	73-22-11	D39926		5		D46144P	A06		YC053-YD170	
1302	20	X1	EP	71-10	73-22-11	D39926		5		D46144P	A06		YL951-YL999, YR301-YR328	
1302	20	X1	EP	61-10	73-22-11	D39926		5		D46144P	A06		YN231-YN501	
1302Z			EP	0-0	73-22-11	D39926		S/R		D46144P	PERG	1F	ALL	
1303	20	X1	EQ	71-9	74-11-11	D39926		3		D46144P	A05		YC051-YC052	
1303	20	X1	EQ	71-7	74-11-11	D39926		3		D46144P	A05		YC053-YD170	
1303	20	X1	EQ	71-10	74-11-11	D39926		3		D46144P	A05		YL951-YL999, YR301-YR328	
1303	20	X1	EQ	61-10	74-11-11	D39926		3		D46144P	A05		YN231-YN501	
1303Z			EQ	0-0	74-11-11	D39926		S/R		D46144P	PERG	1F	ALL	
1304R	20	X5	ER	41-10	26-11-21	D39926		28		D40728J	22		YC051-YC052, YL951-YL999, YR301-YR328	
1304R	20	X5	ER	41-7	26-11-21	D39926		28		D40728J	22		YC053-YD170	
1304R	20	X5	ER	31-9	26-11-21	D39926		28		D40728J	22		YN231-YN501	
1304Z			ER	0-0	26-11-21	D39926		S/R		D40728J	S/R		ALL	
1305R	20	X5	ES	41-10	26-11-21	D39926		29		D40728J	23		YC051-YC052, YL951-YL999, YR301-YR328	
1305R	20	X5	ES	41-7	26-11-21	D39926		29		D40728J	23		YC053-YD170	
1305R	20	X5	ES	31-9	26-11-21	D39926		29		D40728J	23		YN231-YN501	
1305Z			ES	0-0	26-11-21	D39926		S/R		D40728J	S/R		ALL	
2601R	20	RJ	SA	41-10	77-31-21	D39926		17		D40728J	1		YC051-YC052	
2601R	20	RJ	SA	41-7	77-31-21	D39926		17		D40728J	1		YC053-YD153	
2601R	20	RJ	SA	41-7	77-31-21	D39926		6		D40728J	1		YD154-YD170	
2601R	20	RJ	SA	41-10	77-31-21	D39926		6		D40728J	1		YL951-YL999, YR301-YR328	
2601R	20	RJ	SA	31-9	77-31-21	D39926		6		D40728J	1		YN231-YN501	
2601W	20	RJ	SA	0-0	77-31-21	D39926		18		D40728J	2		YC051-YD153	
2601W	20	RJ	SA	0-0	77-31-21	D39926		1		D40728J	2		YD154-YR328	
2601Z			SA	0-0	77-31-21	D39926		7		D40728J	3		ALL	
2602B	24	Y2	SB	41-10	77-12-11	D39926		39		D40728J	4		YC051-YC052, YL951-YL999, YR301-YR328	
2602B	24	Y2	SB	41-7	77-12-11	D39926		39		D40728J	4		YC053-YD170	
2602B	24	Y2	SB	31-9	77-12-11	D39926		39		D40728J	4		YN231-YN501	
2602R	24	Y2	SB	0-0	77-12-11	D39926		19		D40728J	5		ALL	

WIRE LIST

D280A108

91-21-11

Section W6170

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice Effectivity	
W6170	286A6170	RIGHT WING BODY PRESS SEAL TO E/E BAY (continued)			
2602Z		0-0 77-12-11	D39926 S/R	D40728J S/R	ALL
2603B	20 PB SC	41-10 SPARE	D39926 10	D40728J 6	YC051-YC052, YL951-YL999, YR301-YR328
2603B	20 PB SC	41-7 SPARE	D39926 10	D40728J 6	YC053-YD170
2603B	20 PB SC	31-9 SPARE	D39926 10	D40728J 6	YN231-YN501
2603R	20 PB SC	0-0 SPARE	D39926 2	D40728J 7	ALL
2604B	20 PB SD	41-10 SPARE	D39926 11	D40728J 8	YC051-YC052, YL951-YL999, YR301-YR328
2604B	20 PB SD	41-7 SPARE	D39926 11	D40728J 8	YC053-YD170
2604B	20 PB SD	31-9 SPARE	D39926 11	D40728J 8	YN231-YN501
2604R	20 PB SD	0-0 SPARE	D39926 24	D40728J 9	ALL
2605B	20 PB SE	41-10 SPARE	D39926 15	D40728J 15	YC051-YC052, YL951-YL999, YR301-YR328
2605B	20 PB SE	41-7 SPARE	D39926 15	D40728J 15	YC053-YD170
2605B	20 PB SE	31-9 SPARE	D39926 15	D40728J 15	YN231-YN501
2605R	20 PB SE	0-0 SPARE	D39926 16	D40728J 16	ALL
2606B	22 PB SF	71-9 30-21-21	D39926 22	D46144P A03	YC051-YC052
2606B	22 PB SF	71-7 30-21-21	D39926 22	D46144P A03	YC053-YD170
2606B	22 PB SF	71-10 30-21-21	D39926 22	D46144P A03	YL951-YL999, YR301-YR328
2606B	22 PB SF	61-10 30-21-21	D39926 22	D46144P A03	YN231-YN501
2606R	22 PB SF	0-0 30-21-21	D39926 21	D46144P A02	ALL
3601B	24 Y3 A4	41-10 79-31-11	D39926 36	D40728J 12	YC051-YC052, YL951-YL999, YR301-YR328
3601B	24 Y3 A4	41-7 79-31-11	D39926 36	D40728J 12	YC053-YD170
3601B	24 Y3 A4	31-9 79-31-11	D39926 36	D40728J 12	YN231-YN501
3601R	24 Y3 A4	0-0 79-31-11	D39926 35	D40728J 13	ALL
3601Y	24 Y3 A4	0-0 79-31-11	D39926 37	D40728J 14	ALL
3601Z	24 Y3 A4	0-0 79-31-11	D39926 S/R	D40728J S/R	ALL
6001	22 PA	71-9 30-21-21	D39926 23	D46144P A04	YC051-YC052
6001	22 PA	71-7 30-21-21	D39926 23	D46144P A04	YC053-YD170
6001	22 PA	71-10 30-21-21	D39926 23	D46144P A04	YL951-YL999, YR301-YR328
6001	22 CQ	61-10 30-21-21	D39926 23	D46144P A04	YN231-YN501
6002	20 PA	71-9 30-21-21	D39926 38	D46144P A01	YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W6170

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W6170	286A6170				RIGHT WING BODY PRESS SEAL TO E/E BAY (continued)												
6002	20		PA		71-7	30-21-21		D39926	38			D46144P	A01			YC053-YD170	
6002	20		PA		71-10	30-21-21		D39926	38			D46144P	A01			YL951-YL999, YR301-YR328	
6002	20		PA		61-10	30-21-21		D39926	38			D46144P	A01			YN231-YN501	
6003	22		PA		35-4	46-11-51		SP00619		9		D46144P	A07			YL951-YL954, YN231-YN235	
6006	20		CQ		57-2	28-21-11		D39926	30			TB0262Y	A005	1A		YC051-YC052	
6006	20		CQ		57-5	28-21-11		D39926	30			TB0262Y	A005	1A		YC053-YD170	
6006	20		CQ		57-7	28-21-11		D39926	30			TB0262Y	A005	1A		YL951-YL999, YR301-YR328	
6006	20		CQ		47-1	28-21-11		D39926	30			TB0262Y	A005	1A		YN231-YN501	
6007	20		CQ		57-4	28-21-11		D39926	31			TB0262Y	A011	1A		YC051-YC052	
6007	20		CQ		57-7	28-21-11		D39926	31			TB0262Y	A011	1A		YC053-YD170	
6007	20		CQ		57-9	28-21-11		D39926	31			TB0262Y	A011	1A		YL951-YL999, YR301-YR328	
6007	20		CQ		47-3	28-21-11		D39926	31			TB0262Y	A011	1A		YN231-YN501	
6008	20		CQ		57-2	28-21-11		D39926	32			TB0262X	A004	1A		YC051-YC052	
6008	20		CQ		57-4	28-21-11		D39926	32			TB0262X	A004	1A		YC053-YD170	
6008	20		CQ		57-6	28-21-11		D39926	32			TB0262X	A004	1A		YL951-YL999, YR301-YR328	
6008	20		CQ		47-0	28-21-11		D39926	32			TB0262X	A004	1A		YN231-YN501	
6501	24		PK		41-10	31-62-24		D40728J	17			D39926	8			YC051-YC052, YL951-YL999, YR301-YR328	
6501	24		PK		41-7	31-62-24		D40728J	17			D39926	8			YC053-YD170	
6501	24		PK		31-9	31-62-24		D40728J	17			D39926	8			YN231-YN501	
6502	24		PK		41-10	31-62-24		D39926	33			D40728J	10			YC051-YC052, YL951-YL999, YR301-YR328	
6502	24		PK		41-7	31-62-24		D39926	33			D40728J	10			YC053-YD170	
6502	24		PK		31-9	31-62-24		D39926	33			D40728J	10			YN231-YN501	
W6172	286A6172				RIGHT WING BODY PRESS SEAL TOE/E BAY												
0009	18		PA		1-0	78-32-61		D39918	1			GD01232	DC..	1		YC051-YC054	
0009	18		PA		7-10	78-32-61		D39918	1			GD01232	DC..	1		YC055-YL999, YR301-YR328	
0009	18		PA		8-0	78-32-61		D39918	1			GD01232	DC..	1		YN231-YN260	
0009	18		PA		8-3	78-32-61		D39918	1			GD01232	DC..	1		YN501	
0010	18		PA		1-0	78-32-61		D39918	5			GD01232	DC..	1		YC051-YC054	

WIRE LIST

D280A108

91-21-11

Section W6170

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W6172	286A6172				RIGHT WING BODY PRESS SEAL TOE/E BAY (continued)												
0010	18	PA			7-10	78-32-61	D39918		5			GD01232	DC..	1		YC055-YL999, YR301-YR328	
0010	18	PA			8-0	78-32-61	D39918		5			GD01232	DC..	1		YN231-YN260	
0010	18	PA			8-3	78-32-61	D39918		5			GD01232	DC..	1		YN501	
0011	20	PA			1-0	78-32-61	D39918		8			GD01232	DC..	1		YC051-YC054	
0011	20	PA			7-10	78-36-21	D39918		8			GD01232	DC..	1		YC055-YL999, YR301-YR328	
0011	20	PA			8-0	78-36-21	D39918		8			GD01232	DC..	1		YN231-YN260	
0011	20	PA			8-3	78-36-21	D39918		8			GD01232	DC..	1		YN501	
0012	20	PA			1-0	73-21-12	D39918		9			GD01232	DC..	1		YC051-YC054	
0012	20	PA			7-10	73-21-12	D39918		9			GD01232	DC..	1		YC055-YL999, YR301-YR328	
0012	20	PA			8-0	73-21-12	D39918		9			GD01232	DC..	1		YN231-YN260	
0012	20	PA			8-3	73-21-12	D39918		9			GD01232	DC..	1		YN501	
0013	20	PA			1-0	78-36-21	D39918		18			GD01232	DC..	1		YC051-YC054	
0013	20	PA			7-10	78-36-21	D39918		18			GD01232	DC..	1		YC055-YL999, YR301-YR328	
0013	20	PA			8-0	78-36-21	D39918		18			GD01232	DC..	1		YN231-YN260	
0013	20	PA			8-3	78-36-21	D39918		18			GD01232	DC..	1		YN501	
0014	20	PA			1-0	78-35-21	D39918		36			GD01232	DC..	1		YC051-YC054	
0014	20	PA			7-10	78-35-21	D39918		36			GD01232	DC..	1		YC055-YL999, YR301-YR328	
0014	20	PA			8-0	78-35-21	D39918		36			GD01232	DC..	1		YN231-YN260	
0014	20	PA			8-3	78-35-21	D39918		36			GD01232	DC..	1		YN501	
0511	20	CQ			41-7	49-62-11	TB0803X	B002	1A			SP00028		S		YC051-YC054	
0511	20	CQ			41-11	49-62-11	TB0803X	B002	1A			SP00028		S		YC055-YL999, YR301-YR328	
0511	20	CQ			41-10	49-62-11	TB0803X	B002	1A			SP00028		S		YN231-YN501	
1301	24	Y1	EN		72-9	73-21-12	D39918		21			TB0606Y	B005	1A		YC051-YL999, YR301-YR328	
1301	24	Y1	EN		62-8	73-21-12	D39918		21			TB0606Y	B005	1A		YN231-YN260	
1301	24	Y1	EN		62-10	73-21-12	D39918		21			TB0606Y	B005	1A		YN501	
1301Z			EN		0-0	73-21-12	D39918		S/R			GB00606	ST..	1A		ALL	
2601B	18	X2	SA		72-9	78-32-61	D39918		16			TB0606V	B011	1		YC051-YL999, YR301-YR328	
2601B	18	X2	SA		62-9	78-32-61	D39918		16			TB0606V	B011	1		YN231-YN260	
2601B	18	X2	SA		62-11	78-32-61	D39918		16			TB0606V	B011	1		YN501	
2601R	18	X2	SA		0-0	78-32-61	D39918		6			TB0606V	A011	1		ALL	
2601Z			SA		0-0	78-32-61	D39918		S/R			GB00606	ST..	1A		ALL	

WIRE LIST

D280A108

91-21-11

Section W6170

Page 4

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6172	286A6172				RIGHT WING BODY PRESS SEAL TOE/E BAY (continued)										
2602B	18	X2	SB		72-9	78-32-61	D39918		7		TB0606V	B009	1		YC051-YL999, YR301-YR328
2602B	18	X2	SB		62-9	78-32-61	D39918		7		TB0606V	B009	1		YN231-YN260
2602B	18	X2	SB		62-11	78-32-61	D39918		7		TB0606V	B009	1		YN501
2602R	18	X2	SB		0-0	78-32-61	D39918		17		TB0606V	A009	1		ALL
2602Z			SB		0-0	78-32-61	D39918		S/R		GB00606	ST..	1A		ALL
2603B	22	PB	SC		40-3	78-36-21	D39918		19		D40730J		1		YC051-YL999, YR301-YR328
2603B	22	PB	SC		30-3	78-36-21	D39918		19		D40730J		1		YN231-YN260
2603B	22	PB	SC		30-6	78-36-21	D39918		19		D40730J		1		YN501
2603R	22	PB	SC		0-0	78-36-21	D39918		20		D40730J		2		ALL
2604B	22	PB	SD		40-3	78-36-21	D39918		38		D40730J		3		YC051-YL999, YR301-YR328
2604B	22	PB	SD		30-3	78-36-21	D39918		38		D40730J		3		YN231-YN260
2604B	22	PB	SD		30-6	78-36-21	D39918		38		D40730J		3		YN501
2604R	22	PB	SD		0-0	78-36-21	D39918		39		D40730J		4		ALL
2605B	24	Y2	SE		40-3	73-24-12	D39918		35		D40730J		5		YC051-YL999, YR301-YR328
2605B	24	Y2	SE		30-3	73-24-12	D39918		35		D40730J		5		YN231-YN260
2605B	24	Y2	SE		30-6	73-24-12	D39918		35		D40730J		5		YN501
2605R	24	Y2	SE		0-0	73-24-12	D39918		15		D40730J		6		ALL
2605Z			SE		0-0	73-24-12	D39918		S/R		D40730J	S/R			ALL
2606B	24	Y2	SF		40-3	73-24-21	D39918		34		D40730J		7		YC051-YL999, YR301-YR328
2606B	24	Y2	SF		30-3	73-24-21	D39918		34		D40730J		7		YN231-YN260
2606B	24	Y2	SF		30-6	73-24-21	D39918		34		D40730J		7		YN501
2606R	24	Y2	SF		0-0	73-24-21	D39918		33		D40730J		8		ALL
2606Z			SF		0-0	73-24-21	D39918		S/R		D40730J	S/R			ALL
2607B	20	X2	SG		74-3	73-21-21	D39918		27		D11162		5		YC051-YC054
2607B	20	X2	SG		74-9	73-21-21	D39918		27		D11162		5		YC055-YL999, YR301-YR328
2607B	20	X2	SG		64-3	73-21-21	D39918		27		D11162		5		YN231-YN260
2607B	20	X2	SG		64-5	73-21-21	D39918		27		D11162		5		YN501
2607R	20	X2	SG		0-0	73-21-21	D39918		28		D11162		15		ALL
2607Z			SG		0-0	73-21-21	D39918		S/R		D11162	S/R			ALL
2608B	20	X2	SH		74-3	73-21-21	D39918		25		D11162		2		YC051-YC054
2608B	20	X2	SH		74-9	73-21-21	D39918		25		D11162		2		YC055-YL999, YR301-YR328
2608B	20	X2	SH		64-3	73-21-21	D39918		25		D11162		2		YN231-YN260

WIRE LIST

D280A108

91-21-11

Section W6170

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To						
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W6172	286A6172				RIGHT WING BODY PRESS SEAL TOE/E BAY (continued)												
2608B	20	X2	SH		64-5	73-21-21	D39918		25			D11162	2			YN501	
2608R	20	X2	SH		0-0	73-21-21	D39918		24			D11162	10			ALL	
2608Z			SH		0-0	73-21-21	D39918		S/R			D11162	S/R			ALL	
2609B	20	X2	SI		74-3	73-21-21	D39918		11			D11162	7			YC051-YC054	
2609B	20	X2	SI		74-9	73-21-21	D39918		11			D11162	7			YC055-YL999, YR301-YR328	
2609B	20	X2	SI		64-3	73-21-21	D39918		11			D11162	7			YN231-YN260	
2609B	20	X2	SI		64-5	73-21-21	D39918		11			D11162	7			YN501	
2609R	20	X2	SI		0-0	73-21-21	D39918		26			D11162	8			ALL	
2609Z			SI		0-0	73-21-21	D39918		S/R			D11162	S/R			ALL	
2610B	24	Y2	SJ		70-3	73-21-11	D39918		23			D46146P	A02			YC051-YL999, YR301-YR328	
2610B	24	Y2	SJ		60-2	73-21-11	D39918		23			D46146P	A02			YN231-YN260	
2610B	24	Y2	SJ		60-5	73-21-11	D39918		23			D46146P	A02			YN501	
2610R	24	Y2	SJ		0-0	73-21-11	D39918		22			D46146P	A01			ALL	
2610Z			SJ		0-0	73-21-11	D39918		S/R			D46146P	PERG	1F		ALL	
2611B	24	Y2	SK		55-11	73-21-12	D39918		31			TB0262X	B001	1A		YC051-YL999, YR301-YR328	
2611B	24	Y2	SK		45-4	73-21-12	D39918		31			TB0262X	B001	1A		YN231-YN260	
2611B	24	Y2	SK		45-6	73-21-12	D39918		31			TB0262X	B001	1A		YN501	
2611R	24	Y2	SK		0-0	73-21-12	D39918		30			TB0262X	A001	1A		ALL	
2611Z			SK		0-0	73-21-12	D39918		S/R			GB00261	ST..	1A		ALL	
2612B	20	PB	SL		40-3	SPARE	D39918		12			D40730J	9			YC051-YL999, YR301-YR328	
2612B	20	PB	SL		30-3	SPARE	D39918		12			D40730J	9			YN231-YN260	
2612B	20	PB	SL		30-6	SPARE	D39918		12			D40730J	9			YN501	
2612R	20	PB	SL		0-0	SPARE	D39918		3			D40730J	10			ALL	
2613B	20	PB	SM		40-3	SPARE	D39918		14			D40730J	11			YC051-YL999, YR301-YR328	
2613B	20	PB	SM		30-3	SPARE	D39918		14			D40730J	11			YN231-YN260	
2613B	20	PB	SM		30-6	SPARE	D39918		14			D40730J	11			YN501	
2613R	20	PB	SM		0-0	SPARE	D39918		32			D40730J	12			ALL	
2614B	24	Y2	SN		56-0	74-31-11	D39918		29			TB0262Y	B007	1A		YC051-YL999, YR301-YR328	
2614B	24	Y2	SN		45-5	74-31-11	D39918		29			TB0262Y	B007	1A		YN231-YN260	
2614B	24	Y2	SN		45-7	74-31-11	D39918		29			TB0262Y	B007	1A		YN501	
2614R	24	Y2	SN		0-0	74-31-11	D39918		13			TB0262Y	A007	1A		ALL	
2614Z			SN		0-0	74-31-11	D39918		S/R			GB00261	ST..	1A		ALL	

WIRE LIST

D280A108

91-21-11

Section W6170

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W6172	286A6172				RIGHT WING BODY PRESS SEAL TOE/E BAY (continued)												
6001	20		PA		72-9	78-35-21	D39918		37			TB0606Y	A007	1A		YC051-YL999, YR301-YR328	
6001	20		PA		62-8	78-35-21	D39918		37			TB0606Y	A007	1A		YN231-YN260	
6001	20		PA		62-10	78-35-21	D39918		37			TB0606Y	A007	1A		YN501	
6002	20		PA		3-6	73-21-21	D11162		13			GD00815	ST..	1A		YC051-YC054, YN231-YN501	
6002	20		PA		3-4	73-21-21	D11162		13			GD00815	ST..	1A		YC055-YL999, YR301-YR328	
6003	10		CQ		24-1	49-62-11	TB5060B		10	E		SP00030		S		YC051-YC054	
6003	10		CQ		24-7	49-62-11	TB5060B		10	E		SP00030		S		YC055-YL999, YR301-YR328	
6003	10		CQ		24-3	49-62-11	TB5060B		10	E		SP00030		S		YN231-YN501	

WIRE LIST

D280A108

91-21-11

Section W6170

Page 7 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6182	286A6182			ISPC TO P6 (EE-BAY TO PC POWER OUTLET(P6))											
0002	20		PA		20-2	SPARE	D13902		CAP	Y	D13904		CAP	Y	YL951-YL999, YN232-YR328
0003	20		PA		20-2	25-29-11	D13902		3		D13904		3		YL951-YL999, YN232-YR328
0004	20		PA		20-2	SPARE	D13902		CAP	Y	D13904		CAP	Y	YL951-YL999, YN232-YR328
0006	20		PA		20-2	25-29-11	D13902		6		D13904		6		YL951-YL999, YN232-YR328
0007	20		PA		20-2	25-29-11	D13902		7		D13904		7		YL951-YL999, YN232-YR328
0008	20		PA		20-2	25-29-11	D13902		8		D13904		8		YL951-YL999, YN232-YR328
0009	20		PA		20-2	25-29-11	D13902		9		D13904		9		YL951-YL999, YN232-YR328
2001B	20		PB	AA	20-2	25-29-11	D13902		5		D13904		5		YL951-YL999, YN232-YR328
2001R	20		PB	AA	0-0	25-29-11	D13902		1		D13904		1		YL951-YL999, YN232-YR328
YAAA					0-0	25-29-11	D13904		DED		D13902		PERB		YL951-YL999, YN232-YR328

WIRE LIST
D280A108

91-21-11
Section W6180
Page 1 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity	
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W6202	286A6202			RIGHT A/C PACK (STA 536R) DISC TO A/C PACK (SB2)											
0002	20		HA	1-4	33-33-11	S00065		1	G7	*	S00065	4	G7	*	YC051-YD157, YN231-YN501
0002	20		HA	0-7	33-33-11	S00065		1	G7	*	S00065	4	G7	*	YD158-YL999, YR301-YR328
0003	20		HA	1-6	33-33-11	S00065		2	G7	*	SM00003		9		YC051-YC065
0003	20		HA	1-8	33-33-11	S00065		2	G7	*	SM00003		9		YC067-YL999, YR301-YR328
0003	20		HA	1-7	33-33-11	S00065		2	G7	*	SM00003		9		YN231-YN501
0006	20		HA	2-5	33-33-11	L00179	=P	BK			SM00003		9		YC051-YC065
0006	20		HA	2-7	33-33-11	L00179	=P	BK			SM00003		9		YC067-YL999, YR301-YR328
0006	20		HA	2-8	33-33-11	L00179	=P	BK			SM00003		9		YN231-YN501
0007	20		HA	5-1	33-33-11	L00180	=P	BK			SM00003		9		YC051-YC065
0007	20		HA	4-11	33-33-11	L00180	=P	BK			SM00003		9		YC067-YL999, YR301-YR328
0007	20		HA	4-4	33-33-11	L00180	=P	BK			SM00003		9		YN231-YN501
0009	20		HA	12-5	33-33-11	L00181	=P	BK			SM00003		9		YC051-YC065
0009	20		HA	12-3	33-33-11	L00181	=P	BK			SM00003		9		YC067-YL999, YR301-YR328
0009	20		HA	12-0	33-33-11	L00181	=P	BK			SM00003		9		YN231-YN501
0010	20		HA	7-4	33-33-11	GD06120	AC..	GW			L00179	=G	G7		YC051-YL999, YR301-YR328
0010	20		HA	1-10	33-33-11	GD02306	AC..	GW			L00179	=G	G7		YN231-YN501
0011	20		HA	1-6	33-33-11	GD06120	AC..	GW			L00180	=G	G7		YC051-YL999, YR301-YR328
0011	20		HA	6-4	33-33-11	GD02306	AC..	GW			L00180	=G	G7		YN231-YN501
0013	20		HA	1-11	33-33-11	GD06126	AC..	GW			L00181	=G	G7		YC051-YL999, YR301-YR328
0013	20		HA	1-3	33-33-11	GD00566	AC..	GW			L00181	=G	G7		YN231-YN501
0014	20		HA	2-6	21-51-25	GD02344	DC..	GW	*2		D00538		1		YC051-YC065
0014	20		HA	4-0	21-51-25	GD02344	DC..	GW	*2		D00538		1		YC067-YD157
0014	20		HA	2-3	21-51-25	GD02344	DC..	GW	*2		D00538		1		YD158-YL999, YR301-YR328
0014	20		HA	2-2	21-51-25	GD02344	DC..	GW	*1		D00538		1		YN231-YN501
0015	20		HA	2-11	21-51-25	D10058		1			GD02344	DC..	GW	*2	YC051-YC065
0015	20		HA	4-4	21-51-25	D10058		1			GD02344	DC..	GW	*2	YC067-YD157
0015	20		HA	2-6	21-51-25	D10058		1			GD02344	DC..	GW	*2	YD158-YL999, YR301-YR328
0016	20		HA	2-7	21-61-51	D03982		A			GD02344	DC..	GW	*2	YC051-YC065

WIRE LIST

D280A108

91-21-11

Section W6200

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W6202	286A6202	RIGHT A/C PACK (STA 536R) DISC TO A/C PACK (SB2) (continued)			
0016	20	HA	4-1 21-61-51 D03982	A	GD02344 DC.. GW *2 YC067-YD157
0016	20	HA	2-5 21-61-51 D03982	A	GD02344 DC.. GW *2 YD158-YL999, YR301-YR328
1001	20	HE AA	4-10 21-51-24 D40058J	16	D00972 4 YN231-YN501
1001Z		AA	0-0 21-51-24 D40058J	S/R	GD02344 DC.. GW *3 YN231-YN501
1002	20	HE AB	5-5 21-51-24 GD00016	AC.. 1	D00972 5 YN231-YN501
1002Z		AB	0-0 21-51-24 GD00016	ST.. 1	GD02344 DC.. GW *4 YN231-YN501
1005	20	HE AE	6-3 21-51-26 D40058J	5	D00708 4 YN231-YN501
1005Z		AE	0-0 21-51-26 D40058J	S/R	GD02362 ST.. GW YN231-YN501
1006	20	HE AF	7-0 21-51-26 D00704	3	GD00016 AC.. 1 YN231-YN501
1006Z		AF	0-0 21-51-26 GD02342	ST.. GW	GD00016 ST.. 1 YN231-YN501
1007	20	HE AG	2-3 21-51-26 GD00646	AC.. GW *1	D00708 5 YN231-YN501
1007Z		AG	0-0 21-51-26 GD00646	AC.. GW *1	GD02362 ST.. GW YN231-YN501
1008R	20	H9 AH	13-10 26-12-11 D04582J	2	M01912 =B GW YC051-YL999, YR301-YR328
1008R	20	H9 AH	13-9 26-12-11 D04582J	2	M01912 =B GW YN231-YN501
1008Z		AH	0-0 26-12-11 D04582J	S/R	GD02334 ST.. GW *1 ALL
1009R	20	H9 AI	13-10 26-12-11 D04582J	1	M01912 =A GW ALL
1009Z		AI	0-0 26-12-11 D04582J	S/R	GD02334 ST.. GW *1 ALL
1010R	20	H9 AJ	7-2 26-12-11 D00844	=1	D00836 =1 YC051-YC065, YD158-YL999, YR301-YR328
1010R	20	H9 AJ	7-1 26-12-11 D00844	=1	D00836 =1 YC067-YD157
1010Z		AJ	0-0 26-12-11 GD02352	ST.. GW	GD02344 DC.. GW YN231-YN501
1010Z		AJ	0-0 26-12-11 GD02344	DC.. GW	GD02352 ST.. GW YC051-YD153
1010Z		AJ	0-0 26-12-11 GD02344	DC.. GW	GD02352 ST.. GW YD154-YL999, YR301-YR328
1010Z		AJ	0-0 26-12-11 GD02344	DC.. GW	GD02352 ST.. GW YN231-YN501
1011	20	HE AK	13-3 27-83-11 D03188	1	D04582J 3 ALL
1011Z		AK	0-0 27-83-11 GD02338	ST.. GW *1	D04582J S/R ALL
1012	20	HE AL	3-2 27-83-11 D03188	2	GD01148 DC.. GW *1 YC051-YL999, YR301-YR328
1012	20	HE AL	3-1 27-83-11 D03188	2	GD01148 DC.. GW *1 YN231-YN501
1012Z		AL	0-0 27-83-11 GD02338	ST.. GW	GD01148 DC.. GW *1 ALL
1013	20	HE AM	14-1 27-83-21 D40058J	1	D40058J 7 ALL
1013Z		AM	0-0 27-83-21 GD02338	ST.. GW *2	D40058J S/R ALL
1014	20	HE AN	1-10 33-33-11 D40058J	9	S00065 1 G7 * YC051-YL999, YR301-YR328
1014	20	HE AN	1-11 33-33-11 D40058J	9	S00065 1 G7 * YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W6200

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6202	286A6202			RIGHT A/C PACK (STA 536R) DISC TO A/C PACK (SB2) (continued)											
1014Z				AN	0-0	33-33-11	D40058J	S/R			GD02350	ST..	GW	*1	ALL
1015	20	HE	AP		1-10	33-33-11	D40058J	11			S00065	4	G7	*	YC051-YL999, YR301-YR328
1015	20	HE	AP		1-11	33-33-11	D40058J	11			S00065	4	G7	*	YN231-YN501
1015Z				AP	0-0	33-33-11	D40058J	S/R			GD02350	ST..	GW	*2	ALL
1016	20	HE	AQ		1-10	33-33-11	D40058J	12			S00065	5	G7		YC051-YL999, YR301-YR328
1016	20	HE	AQ		1-11	33-33-11	D40058J	12			S00065	5	G7		YN231-YN501
1016Z				AQ	0-0	33-33-11	D40058J	S/R			GD02350	ST..	GW	*2	ALL
1017	20	HE	AR		1-10	33-33-11	D04582J	4			S00065	2	G7	*	YC051-YL999, YR301-YR328
1017	20	HE	AR		1-11	33-33-11	D04582J	4			S00065	2	G7	*	YN231-YN501
1017Z				AR	0-0	33-33-11	D04582J	S/R			GD02350	ST..	GW	*1	ALL
1018	20	HE	AS		3-10	30-71-11	D40058J	4			SP00530				YC051-YD157
1018	20	HE	AS		4-1	30-71-11	D40058J	4			SP00530				YD158-YL999, YR301-YR328
1018	20	HE	AS		4-3	30-71-11	D40058J	22			SP00530				YN231-YN501
1018Z				AS	0-0	30-71-11	D40058J	S/R			GD02354	ST..	GW		YC051-YD153, YN231-YN501
1018Z				AS	0-0	30-71-11	D40058J	S/R			GD02354	ST..	GW	*1	YD154-YL999, YR301-YR328
1025	20	HE	AZ		6-3	21-51-25	D04582J	5			D00536	2			YN231-YN501
1025Z				AZ	0-0	21-51-25	D04582J	S/R			GD02340	ST..	GW		YN231-YN501
1026	20	HE	BA		3-7	21-51-25	GD02344	DC..	GW	*1	D00536	1			YN231-YN501
1026Z				BA	0-0	21-51-25	GD02344	DC..	GW	*1	GD02340	ST..	GW		YN231-YN501
1027	20	HE	BB		7-3	21-51-25	D04582J	7			D00538	2			YC051-YC065
1027	20	HE	BB		6-8	21-51-25	D04582J	7			D00538	2			YC067-YL999, YR301-YR328
1027	20	HE	BB		6-6	21-51-25	D04582J	7			D00538	2			YN231-YN501
1027Z				BB	0-0	21-51-25	D04582J	S/R			GD02344	DC..	GW	*5	YC051-YL999, YR301-YR328
1027Z				BB	0-0	21-51-25	D04582J	S/R			GD02344	DC..	GW		YN231-YN501
1029	20	HE	BD		4-0	27-83-21	D03190	2			GD01148	DC..	GW	*2	YC051-YL999, YR301-YR328
1029	20	HE	BD		3-11	27-83-21	D03190	2			GD01148	DC..	GW	*2	YN231-YN501
1029Z				BD	0-0	27-83-21	GD02338	ST..	GW	*2	GD01148	DC..	GW	*2	ALL
1030	20	HE	BE		3-7	36-21-11	D00098	3			D40058J	1			YC051-YC065
1030	20	HE	BE		3-6	36-21-11	D00098	3			D40058J	1			YC067-YD157

WIRE LIST

D280A108

91-21-11

Section W6200

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description		From				To					
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6202	286A6202			RIGHT A/C PACK (STA 536R) DISC TO A/C PACK (SB2) (continued)											
1030	20	HE	BE		3-11	36-21-11	D00098		3		D40058J		1		YD158-YL999, YR301-YR328
1030	20	HE	BE		3-10	36-21-11	D00098		3		D40058J		1		YN231-YN501
1030Z			BE		0-0	36-21-11	GD02352	ST..	GW		D40058J	S/R			ALL
1032	20	HE	BG		2-10	21-51-22	D03872		3		GD00556	AC..	GW	*1	YC051-YC057
1032	20	HE	BG		2-3	21-51-22	D03872		3		GD00556	AC..	GW	*1	YC058-YL968
1032	20	HE	BG		2-4	21-51-22	D03872		3		GD00556	AC..	GW	*1	YL969-YL999, YR301-YR328
1032Z			BG		0-0	21-51-22	D03872			AH	GD00556	AC..	GW	*1	YC051-YD153
1032Z			BG		0-0	21-51-22	GD06124	ST..	GW	*	GD00556	AC..	GW	*1	YD154-YL999, YR301-YR328
1033	20	HE	BH		2-0	21-51-22	D03872		5		GD00374	DC..	GW	*1	YC051-YL968
1033	20	HE	BH		1-11	21-51-22	D03872		5		GD00374	DC..	GW	*1	YL969-YL999, YR301-YR328
1033Z			BH		0-0	21-51-22	D03872			AH	GD00374	DC..	GW	*1	YC051-YD153
1033Z			BH		0-0	21-51-22	GD06124	ST..	GW	*	GD00374	DC..	GW	*1	YD154-YL999, YR301-YR328
1034	20	HE	BI		7-8	21-51-25	D04582J		5		D10058		2		YC051-YC065
1034	20	HE	BI		7-0	21-51-25	D04582J		5		D10058		2		YC067-YD157
1034	20	HE	BI		6-11	21-51-25	D04582J		5		D10058		2		YD158-YL999, YR301-YR328
1034Z			BI		0-0	21-51-25	D04582J			S/R	GD02344	DC..	GW	*5	YC051-YL999, YR301-YR328
1038	20	HE	BM		5-1	21-61-13	D03888		3		GD00016	AC..	1		YC051-YD157
1038	20	HE	BM		6-5	21-61-13	D03888		3		GD00016	AC..	1		YD158-YL999, YR301-YR328
1038Z			BM		0-0	21-61-13	D03888			AK	GD00016	ST..	1		YC051-YD153
1038Z			BM		0-0	21-61-13	GD02354	ST..	GW	*1	GD00016	ST..	1		YD154-YL999, YR301-YR328
1039	20	HE	CN		4-7	21-61-13	D04582J		10		D03888		10		YC051-YC065
1039	20	HE	CN		4-8	21-61-13	D04582J		10		D03888		10		YC067-YD157
1039	20	HE	CN		5-1	21-61-13	D04582J		10		D03888		10		YD158-YL999, YR301-YR328
1039Z			CN		0-0	21-61-13	D04582J			S/R	D03888				YC051-YD153
1039Z			CN		0-0	21-61-13	D04582J			S/R	GD02354	ST..	GW	AK *2	YD154-YL999, YR301-YR328
1040	20	HE	CP		5-1	21-61-13	D03888		5		GD00016	DC..	1		YC051-YD157
1040	20	HE	CP		6-5	21-61-13	D03888		5		GD00016	DC..	1		YD158-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W6200

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To															
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity				
W6202	286A6202	RIGHT A/C PACK (STA 536R) DISC TO A/C PACK (SB2) (continued)																	
1040Z				CP	0-0	21-61-13	D03888			AK	GD00016	ST..	1					YC051-YD153	
1040Z				CP	0-0	21-61-13	GD02354	ST..	GW	*2	GD00016	ST..	1					YD154-YL999, YR301-YR328	
1041	20	HE	BR		4-4	21-61-13	D40058J	18			D03888	11						YC051-YC065	
1041	20	HE	BR		4-5	21-61-13	D40058J	18			D03888	11						YC067-YD157	
1041	20	HE	BR		5-2	21-61-13	D40058J	18			D03888	11						YD158-YL999, YR301-YR328	
1041Z				BR	0-0	21-61-13	D40058J	S/R			D03888							YC051-YD153	
1041Z				BR	0-0	21-61-13	D40058J	S/R			GD02354	ST..	GW					YD154-YL999, YR301-YR328	
1042	20	HE	BS		4-6	21-61-14	D03890	3			GD00016	AC..	1					YC051-YC065	
1042	20	HE	BS		3-5	21-61-14	D03890	3			GD00016	AC..	1					YC067-YD157	
1042	20	HE	BS		2-11	21-61-14	D03890	3			GD00016	AC..	1					YD158-YL999, YR301-YR328	
1042Z				BS	0-0	21-61-14	D03890			AL	GD00016	ST..	1					YC051-YD153	
1042Z				BS	0-0	21-61-14	D03890	DED			GD00016	ST..	1					YD154-YL999, YR301-YR328	
1043	20	HE	BT		4-0	21-61-14	D04582J	13			D03890	10						YC051-YC065	
1043	20	HE	BT		2-8	21-61-14	D04582J	13			D03890	10						YC067-YD157	
1043	20	HE	BT		3-8	21-61-14	D04582J	13			D03890	10						YD158-YL999, YR301-YR328	
1043Z				BT	0-0	21-61-14	D04582J	S/R			D03890							YC051-YD153	
1043Z				BT	0-0	21-61-14	D04582J	S/R			D03890	DED						YD154-YL999, YR301-YR328	
1045	20	HE	BW		4-6	21-61-14	D03890	5			GD00016	DC..	1					YC051-YC065	
1045	20	HE	BW		3-5	21-61-14	D03890	5			GD00016	DC..	1					YC067-YD157	
1045	20	HE	BW		2-11	21-61-14	D03890	5			GD00016	DC..	1					YD158-YL999, YR301-YR328	
1045Z				BW	0-0	21-61-14	D03890			AL	GD00016	ST..	1					YC051-YD153	
1045Z				BW	0-0	21-61-14	D03890	DED			GD00016	ST..	1					YD154-YL999, YR301-YR328	
1046	20	HE	BX		3-9	21-61-14	D40058J	27			D03890	11						YC051-YC065, YD158-YL999, YR301-YR328	
1046	20	HE	BX		2-9	21-61-14	D40058J	27			D03890	11						YC067-YD157	
1046Z				BX	0-0	21-61-14	D40058J	S/R			D03890							YC051-YD153	
1046Z				BX	0-0	21-61-14	D40058J	S/R			D03890	DED						YD154-YL999, YR301-YR328	
1049	20	HE	CA		7-4	21-61-51	D03982	B			D40058J	10						YC051-YC065	

WIRE LIST

D280A108

91-21-11

Section W6200

Page 5

Nov 12/2012



WIRE LIST
D280A108

91-21-11
Section W6200
Page 6
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6202	286A6202			RIGHT A/C PACK (STA 536R) DISC TO A/C PACK (SB2) (continued)											
2077B	20	HF	JB		16-5	21-51-22	D40058J	21			D03872	4			YC051-YC057
2077B	20	HF	JB		16-0	21-51-22	D40058J	21			D03872	4			YC058-YL999, YR301-YR328
2077R	20	HF	JB		0-0	21-51-22	D40058J	22			D03872	12			YC051-YL999, YR301-YR328
2077Z			JB		0-0	21-51-22	D40058J	S/R			D03872				YC051-YD153
2077Z			JB		0-0	21-51-22	D40058J	S/R			GD06124	ST..	GW	AH *	YD154-YL999, YR301-YR328
2078B	20	HF	JC		16-5	21-51-22	D40058J	15			D03872	1			YC051-YC057
2078B	20	HF	JC		16-0	21-51-22	D40058J	15			D03872	1			YC058-YL999, YR301-YR328
2078R	20	HF	JC		0-0	21-51-22	D40058J	20			D03872	2			YC051-YL999, YR301-YR328
2078Z			JC		0-0	21-51-22	D40058J	S/R			D03872				YC051-YD153
2078Z			JC		0-0	21-51-22	D40058J	S/R			GD06124	ST..	GW	AH *	YD154-YL999, YR301-YR328
2079B	20	HF	JD		7-8	21-51-22	D40058J	23			D03876	1			YC051-YC065
2079B	20	HF	JD		7-1	21-51-22	D40058J	23			D03876	1			YC067-YL999, YR301-YR328
2079R	20	HF	JD		0-0	21-51-22	D40058J	24			D03876	2			YC051-YL999, YR301-YR328
2079Z			JD		0-0	21-51-22	D40058J	S/R			GD02344	DC..	GW	*1	YC051-YL999, YR301-YR328
2080B	20	HF	JE		7-8	21-51-23	D40058J	6			D03876	3			YC051-YC065
2080B	20	HF	JE		7-1	21-51-23	D40058J	6			D03876	3			YC067-YL999, YR301-YR328
2080R	20	HF	JE		0-0	21-51-23	D40058J	8			D03876	4			YC051-YL999, YR301-YR328
2080Z			JE		0-0	21-51-23	D40058J	S/R			GD02344	DC..	GW	*1	YC051-YL999, YR301-YR328
2081B	20	HF	JF		14-8	21-51-23	D40058J	13			D03874	3			YC051-YD157
2081B	20	HF	JF		14-9	21-51-23	D40058J	13			D03874	3			YD158-YL999, YR301-YR328
2081R	20	HF	JF		0-0	21-51-23	D40058J	19			D03874	1			YC051-YL999, YR301-YR328
2081Z			JF		0-0	21-51-23	D40058J	S/R			GD06128	ST..	GW		YC051-YL999, YR301-YR328
2082B	20	HF	JG		6-1	21-51-24	D40058J	16			D03918	1			YC051-YL968

WIRE LIST

D280A108

91-21-11

Section W6200

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6202	286A6202				RIGHT A/C PACK (STA 536R) DISC TO A/C PACK (SB2) (continued)										
2082B	20	HF	JG		6-3	21-51-24	D40058J		16		D03918		1		YL969-YL999, YR301-YR328
2082R	20	HF	JG		0-0	21-51-24	D40058J		17		D03918		2		YC051-YL999, YR301-YR328
2082Z			JG		0-0	21-51-24	D40058J		S/R		GD06122	ST..	GW		YC051-YL999, YR301-YR328
2083B	20	HF	JH		4-7	21-61-13	D04582J		8		D03888		1		YC051-YC065
2083B	20	HF	JH		4-8	21-61-13	D04582J		8		D03888		1		YC067-YD157
2083B	20	HF	JH		5-1	21-61-13	D04582J		8		D03888		1		YD158-YL999, YR301-YR328
2083R	20	HF	JH		0-0	21-61-13	D04582J		9		D03888		2		YC051-YL999, YR301-YR328
2083Z			JH		0-0	21-61-13	D04582J		S/R		D03888				YC051-YD153
2083Z			JH		0-0	21-61-13	D04582J		S/R		GD02354	ST..	GW		YD154-YL999, YR301-YR328
2084B	20	HF	JI		4-4	21-61-13	D40058J		25		D03888		12		YC051-YC065
2084B	20	HF	JI		4-5	21-61-13	D40058J		25		D03888		12		YC067-YD157
2084B	20	HF	JI		5-2	21-61-13	D40058J		25		D03888		12		YD158-YL999, YR301-YR328
2084R	20	HF	JI		0-0	21-61-13	D40058J		26		D03888		4		YC051-YL999, YR301-YR328
2084Z			JI		0-0	21-61-13	D40058J		S/R		D03888				YC051-YD153
2084Z			JI		0-0	21-61-13	D40058J		S/R		GD02354	ST..	GW		YD154-YL999, YR301-YR328
2085B	20	HF	JJ		4-0	21-61-14	D04582J		11		D03890		1		YC051-YC065
2085B	20	HF	JJ		2-8	21-61-14	D04582J		11		D03890		1		YC067-YD157
2085B	20	HF	JJ		3-8	21-61-14	D04582J		11		D03890		1		YD158-YL999, YR301-YR328
2085R	20	HF	JJ		0-0	21-61-14	D04582J		12		D03890		2		YC051-YL999, YR301-YR328
2085Z			JJ		0-0	21-61-14	D04582J		S/R		D03890				YC051-YD153
2085Z			JJ		0-0	21-61-14	D04582J		S/R		D03890	DED			YD154-YL999, YR301-YR328
2086B	20	HF	JK		3-9	21-61-14	D40058J		28		D03890		12		YC051-YC065, YD158-YL999, YR301-YR328
2086B	20	HF	JK		2-9	21-61-14	D40058J		28		D03890		12		YC067-YD157
2086R	20	HF	JK		0-0	21-61-14	D40058J		29		D03890		4		YC051-YL999, YR301-YR328

WIRE LIST
D280A108

91-21-11
Section W6200
Page 8
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6202		286A6202			RIGHT A/C PACK (STA 536R) DISC TO A/C PACK (SB2) (continued)											
2086Z					JK	0-0	21-61-14	D40058J	S/R			D03890			AL	YC051-YD153
2086Z					JK	0-0	21-61-14	D40058J	S/R			D03890	DED			YD154-YL999, YR301-YR328
5501	20	HA				0-7	21-51-26	TB0636Y	A001	1A		TB0636Y	B003	1A		YN231-YN501
5502	20	HA				1-6	21-61-22	D00170		1		GD00374	DC..	GW		YN231-YN501
5515	20	HA				1-10	36-21-11	D00098		5		GD02352	ST..	GW		YC051-YC057
5515	20	HA				1-11	36-21-11	D00098		5		GD02352	ST..	GW		YC051-YL999, YR301-YR328
5515	20	HA				2-0	36-21-11	D00098		5		GD02352	ST..	GW		YN231-YN501
5552	20	HA				1-3	21-51-22	D03872		13		GD06124	ST..	GW		YC051-YL999, YR301-YR328
5553	20	HA				2-3	21-51-23	D03874		2		GD06128	ST..	GW		YC051-YL999, YR301-YR328
5556	20	HA				2-3	30-71-11	D11920		2		GD02306	AC..	GW	*	ALL
5557	20	HA				3-2	30-71-11	SP00572		9		GD02306	AC..	GW	*	ALL
5562	20	HA				0-6	21-61-13	D03888			AK	SM00001		9		YC051-YD153
5563	20	HA				0-6	21-61-13	D03888		13		SM00001		9		YC051-YD153
5564	20	HA				3-0	21-61-13	SM00001		9		GD02354	ST..	GW	*1	YC051-YC065
5564	20	HA				3-2	21-61-13	SM00001		9		GD02354	ST..	GW	*1	YC067-YD153
5564	20	HA				3-5	21-61-13	D03888		13		GD02354	ST..	GW	*1	YD154-YD157
5564	20	HA				3-11	21-61-13	D03888		13		GD02354	ST..	GW	*1	YD158-YL999, YR301-YR328
5565	20	HA				0-6	21-61-14	D03890			AL	SM00002		9		YC051-YD153
5566	20	HA				0-6	21-61-14	D03890		13		SM00002		9		YC051-YD153
5567	20	HA				2-4	21-61-14	SM00002		9		GD02354	ST..	GW	*1	YC051-YD153
5567	20	HA				2-11	21-61-14	D03890		13		GD02354	ST..	GW	*1	YD154-YD157
5567	20	HA				3-11	21-61-14	D03890		13		GD02354	ST..	GW	*1	YD158-YL999, YR301-YR328
5567	20	HA				2-0	21-61-22	D00522		3		GD00556	AC..	GW		YN231-YN501
5568	20	HA				3-6	21-51-26	D00712		1		TB0636Y	A001	1A		YN231-YN501
5569	20	HA				3-6	21-51-26	D00712		2		TB0636Y	B001	1A		YN231-YN501
5570	20	HA				6-9	21-51-26	D00708		7		TB0636Y	A003	1A		YN231-YN501
5571	20	HA				6-9	21-51-26	D00708		6		TB0636Y	B001	1A		YN231-YN501
A-AA						0-0	30-71-11	SP00530		9		M01951	=P			ALL
A-AB						0-0	30-71-11	SP00570		9		M01951	=G			ALL
A-AC						0-0	30-71-11	SP00570		9		M00820	=P			ALL
A-AD						0-0	30-71-11	M00820	=G			SP00572		9		ALL
FRAH						0-0	21-51-22	D03872			AH	GD06124	ST..	GW		YC051-YD153

WIRE LIST

D280A108

91-21-11

Section W6200

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6204	286A6204				CABIN PRESSURE OUTFLOW VALVE TO E/E BAY (RB2)										
1001	20	X1	AA		107-11	21-31-23	D40066P	A02			D10734	L			YC051-YL999, YR301-YR328
1001	20	X1	AA		88-8	21-31-23	D40066P	A02			D10734	L			YN231-YN501
1001Z			AA		0-0	21-31-23	D40066P	PERG	1F		GD03740	ST..	1		ALL
2001B	24	Y2	GA		107-11	21-31-23	D40066P	A04			D10734	P			YC051-YL999, YR301-YR328
2001B	24	Y2	GA		88-8	21-31-23	D40066P	A04			D10734	P			YN231-YN501
2001R	24	Y2	GA		0-0	21-31-23	D40066P	A03			D10734	R			ALL
2001Z			GA		0-0	21-31-23	D40066P	PERG	1F		GD03740	ST..	1		ALL
2002B	24	Y2	GB		107-11	21-31-23	D40066P	A06			D10734	M			YC051-YL999, YR301-YR328
2002B	24	Y2	GB		88-8	21-31-23	D40066P	A06			D10734	M			YN231-YN501
2002R	24	Y2	GB		0-0	21-31-23	D40066P	A05			D10734	N			ALL
2002Z			GB		0-0	21-31-23	D40066P	PERG	1F		GD03740	ST..	1		ALL
2003B	24	PL	GC		2-0	21-31-23	D10734	E			D10736	E			YC051-YL999, YR301-YR328
2003B	24	PL	GC		2-1	21-31-23	D10734	E			D10736	E			YN231-YN501
2003R	24	PL	GC		0-0	21-31-23	D10734	F			D10736	F			ALL
3001B	24	PM	WA		2-0	21-31-23	D10734	B			D10736	B			YC051-YL999, YR301-YR328
3001B	24	PM	WA		2-1	21-31-23	D10734	B			D10736	B			YN231-YN501
3001R	24	PM	WA		0-0	21-31-23	D10734	C			D10736	C			ALL
3001Y	24	PM	WA		0-0	21-31-23	D10734	A			D10736	A			ALL
5501	20	PA			107-11	21-31-23	D10734	K			D40066P	A01			YC051-YL999, YR301-YR328
5501	20	PA			88-8	21-31-23	D10734	K			D40066P	A01			YN231-YN501
5502	24	PK			107-11	21-31-23	D40066P	A07			D10734	C-			YC051-YL999, YR301-YR328
5502	24	PK			88-8	21-31-23	D40066P	A07			D10734	C-			YN231-YN501
5503	20	PA			2-0	21-31-23	D10736	H			GD03740	ST..	1		YC051-YL999, YR301-YR328
5503	20	PA			1-10	21-31-23	D10736	H			GD03740	ST..	1		YN231-YN501
5504	20	PA			2-5	21-31-23	D10734	G			GD03740	ST..	1		YC051-YL999, YR301-YR328
5504	20	PA			2-4	21-31-23	D10734	G			GD03740	ST..	1		YN231-YN501
5505	20	PA			2-5	21-31-23	D10734	B-			GD03740	DC..	1		YC051-YL999, YR301-YR328
5505	20	PA			2-4	21-31-23	D10734	B-			GD03740	DC..	1		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W6200

Page 10

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	Diagram	From	To			Effectivity						
	Wire No.	GA	CO TY			Fam	FT-IN	Equip	Term		Type	Splice	Equip	Term	Type	Splice
W6204	286A6204			CABIN PRESSURE OUTFLOW VALVE TO E/E BAY (RB2) (continued)												
5506	20	PA		2-5	21-31-23	D10734	J			GD03740	DC..	1			YC051-YL999, YR301-YR328 YN231-YN501	
5506	20	PA		2-4	21-31-23	D10734	J			GD03740	DC..	1				
W6206	286A6206			P8 TO MISC EQUIPMENT (RN2)												
0009	22	PA		12-0	52-51-11	D03428	9			D40816P	9				YC051-YD154	
0010	22	PA		12-0	52-51-11	D03428	10			D40816P	11				YC051-YD154	
0011	22	PA		3-8	52-51-11	D03428	9			GD00807	DC..	1A			YD155-YR328	
0012	22	PA		12-0	52-51-11	D03428	10			D40816P	5				YD155-YR328	
0013	22	PA		4-5	52-51-11	D03428	13			TB0803X	B001	1A			YC051-YD154	
0014	22	PA		12-0	52-51-11	D03428	13			D40816P	6				YD155-YR328	
0015	22	PA		12-0	52-51-11	D03428	7			D40816P	8				YD155-YR328	
0016	22	PA		12-0	52-51-11	D03428	14			D40816P	12				YD155-YR328	
0502	20	PA		6-8	27-41-11	TB0806Z	A017	1A		D03428	17				ALL	
0503	20	PA		6-8	27-41-11	TB0806Z	B017	1A		D03428	16				ALL	
0504	20	PA		6-8	27-41-11	TB0806Z	A021	1A		D03428	15				ALL	
0505	20	PA		4-3	27-41-11	D03428	5			TB0803Y	B011	1A			ALL	
0506	20	PA		4-3	27-41-11	D03428	4			TB0803Y	A011	1A			ALL	
0507	20	PA		4-3	27-41-11	D03428	3			TB0803Y	B009	1A			ALL	
5501	20	CQ		11-2	33-11-33	T00362	HV	E		D40816P	3				ALL	
5502	16	CQ		1-5	33-11-33	GD00817	AC..	1		T00362	GND	E			ALL	
5503	16	CQ		3-4	33-11-33	TB0801V	B011	1		T00362	LV1	E	*		YC051-YC052	
5503	16	CQ		3-2	33-11-33	TB0801W	B017	1		T00362	LV1	E	*		YC053-YR328	
5504	16	CQ		3-2	33-11-33	D03768	B3			TB0801V	B011	1			YC051-YC052	
5504	16	CQ		3-0	33-11-33	D03768	B3			TB0801W	B017	1			YC053-YR328	
5505	16	PA		3-0	33-11-33	D03768	B1			C00205	=L	D			ALL	
5506	16	CQ		3-2	33-11-33	D03768	C3			TB0801V	B011	1			YC051-YC052	
5506	16	CQ		3-0	33-11-33	D03768	C3			TB0801W	B017	1			YC053-YR328	
5507	16	PA		3-1	33-11-33	D03768	C1			C01097	=L	D			ALL	
5508	16	PA		1-3	33-11-33	D03768	X2			GD00817	AC..	1			ALL	
5509	16	PA		3-2	33-11-33	D03768	X1			TB0801V	B009	1			ALL	
5510	16	PA		2-11	33-11-33	D03768	B2			TB0801W	B021	1			ALL	
5511	16	PA		3-3	33-11-33	D03768	C2			TB0801W	A005	1			ALL	
5512	16	PA		10-8	33-11-33	D40816P	4			TB0801V	B009	1			ALL	
5513	14	PA		3-2	33-11-41	C00205	=B	D		T00040	LV	E	*		ALL	
5515	14	PA		3-2	33-11-41	C01097	=B	D		T00040	LV	E	*		ALL	
5516	14	PA		3-2	33-11-41	C01115	=B	D		T00040	LV	E	*		ALL	
5517	16	PA		2-3	33-11-41	C01097	=L	D	*	TB0801W	A021	1			ALL	
5518	16	PA		2-4	33-11-41	C01097	=L	D	*	TB0801W	A017	1			ALL	

WIRE LIST

D280A108

91-21-11

Section W6200

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6206	286A6206				P8 TO MISC EQUIPMENT (RN2) (continued)										
5519	16	PA			2-5	33-11-41	C01115	=L	D	*	TB0801W	A013	1		ALL
5520	16	PA			2-5	33-11-41	C01115	=L	D	*	TB0801W	B013	1		ALL
5521	16	PA			3-5	33-11-41	T00040	HV	E	*	TB0801V	A009	1		YC051-YD158
5521	16	PA			2-6	33-11-41	C00320	=L	D	*	TB0801V	A009	1		YD160-YR328
5522	16	PA			1-3	33-11-41	T00040	GND	E		GD00817	AC..	1		ALL
5528	16	PA			3-11	33-11-41	D03432				TB0801V	B009	1		ALL
5529	16	PA			3-4	33-11-41	D03432		10		GD00817	AC..	1		ALL
5530	16	PA			3-4	33-11-41	D03432		1		GD00817	AC..	1		ALL
5531	16	PA			3-7	33-11-41	D03432		3		T00040	HV	E	*	YC051-YD158
5531	16	PA			3-7	33-11-41	D03432		3		T00040	HV	E		YD160-YR328
5532	16	PA			3-9	33-11-41	D03432		2		C00205	=L	D		ALL
5533	20	PA			3-9	33-11-41	D03428		2		TB0801W	A017	1		ALL
5534	20	PA			3-9	33-11-41	D03428		1		GD00805	AC..	1A		ALL
5535	14	PA			3-2	33-11-41	T00040	LV	E		C00320	=B	D		ALL
5536	16	PA			2-7	33-11-41	C00320	=L	D		TB0801W	B005	1		YC051-YD158
5536	16	PA			2-7	33-11-41	C00320	=L	D	*	TB0801W	B005	1		YD160-YR328
5537	18	PA			11-8	33-14-12	D03432		7		D40816P		18		ALL
5538	18	PA			3-4	33-14-12	D03432		5		GD00817	AC..	1		ALL
5539	18	PA			11-8	33-14-12	D03432		6		D40816P		10		ALL
5540	20	CQ			4-5	33-18-61	D03428		12		TB0803X	A001	1A		YC051-YD154
5541	20	CQ			4-0	33-18-61	D03428		8		TB0804Z	A021	1A		YC051-YD154
5542	20	PA			6-4	33-14-11	T00362	LV1	E	*	TB0806Y	B009	1A		ALL
5543	16	CQ			3-0	33-11-33	TB0801W	B017	1		D03768	D3			YD158-YR328
5544	16	PA			3-0	33-11-33	D03768	D1			C01115	=L	D		YD158-YR328
5545	16	PA			3-2	33-11-33	D03768	D2			TB0801V	B011	1		YD158-YR328
5546	16	CQ			3-0	33-11-33	TB0801W	B017	1		D03768	A3			YC053-YR328
5547	16	PA			3-1	33-11-33	D03768	A1			C00320	=L	D		YC053-YR328
5548	16	PA			3-2	33-11-33	D03768	A2			TB0801V	A011	1		YC053-YR328
5552	20	CQ			4-0	33-18-61	D03428		12		TB0804Z	B021	1A		YD155-YR328
5554	20	CQ			4-3	33-18-61	D03428		8		TB0803Y	A009	1A		YD155-YR328
W6208	286A6208				P8 TO MISC EQUIPMENT										
0001	18	PA			30-7	33-42-11	D40528J		21		D40228P	F			YC051-YD158, YL951-YR328
0003	16	PA			30-7	33-45-11	D40528J		23		D40228P	K			YC051-YD158, YL951-YR328
0500	24	PK			30-4	27-21-11	D03116		4		D40222P	A16			YD154-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W6200

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6208	286A6208				P8 TO MISC EQUIPMENT (continued)										
0501	24		PK		30-4	27-21-11	D03116		7		D40222P	B16			YD154-YD158, YL951-YR328
0502	24		PK		30-5	27-11-11	D02930		11		D40222P	A15			YD154-YD158, YL951-YR328
0503	24		PK		30-5	27-11-11	D02930		12		D40222P	A01			YC051-YD158, YL951-YR328
0504	24		PK		30-5	27-11-11	D02930		4		D40222P	A02			YC051-YD158, YL951-YR328
0505	24		PK		30-5	27-11-11	D02930		7		D40222P	A03			YC051-YD158, YL951-YR328
0506	24		PK		14-9	27-21-11	D40820P		13		D03116	1			YC051-YD158, YL951-YR328
0507	24		PK		30-4	27-21-11	D03116		10		D40222P	A04			YC051-YD158, YL951-YR328
0508	24		PK		30-4	27-21-11	D03116		12		D40222P	A05			YC051-YD158, YL951-YR328
0509	24		PK		30-4	27-21-11	D03116		8		D40222P	A06			YC051-YD158, YL951-YR328
0510	20		PA		4-2	27-21-11	D03116		5		GD00811	AC..	1A		YC051-YD158, YL951-YR328
0511	20		PA		4-2	27-21-11	D03116		6		GD00811	ST..	1A		YC051-YD158, YL951-YR328
0512	16		PA		12-0	33-45-11	D40820P		10		TB0606V	B013	1		YC051-YD158
0512	16		PA		12-0	SPARE	D40820P		10		TB0606V	B013	1		YL951-YR328
0513	20		PA		13-0	27-28-11	GD00801		AC..	1A	D40818P	A09			YC051-YD158, YL951-YR328
0515	20		PA		4-5	27-28-11	D02934		4		GD00801	AC..	1A		YC051-YD158, YL951-YR328
0516	20		PA		4-5	27-28-11	D02934		6		GD00801	ST..	1A		YC051-YD158, YL951-YR328
0517	20		PA		6-5	27-41-11	TB0806Y		A009	1A	D00698	12			YC051-YC052
0517	20		PA		6-2	27-41-11	TB0806Y		A009	1A	D00698	12			YC053-YD158, YL951-YR328
0518	20		PA		2-2	27-41-11	TB0803Y		B009	1A	D00698	7			YC051-YD158, YL951-YR328
0519	20		PA		2-2	27-41-11	TB0803Y		A011	1A	D00698	6			YC051-YD158, YL951-YR328
0520	20		PA		2-2	27-41-11	TB0803Y		B011	1A	D00698	5			YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W6200

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W6208	286A6208				P8 TO MISC EQUIPMENT (continued)											
0521	20		PA		3-4		27-41-11	D00698		11		GD00809	DC..	1A		YC051-YD153
0521	20		PA		2-7		27-41-11	D00698		11		GD00809	DC..	1A		YD154-YD158, YL951-YR328
0522	20		PA		3-4		27-41-11	D00698		9		GD00809	DC..	1A		YC051-YD153
0522	20		PA		2-7		27-41-11	D00698		9		GD00809	DC..	1A		YD154-YD158, YL951-YR328
0523	20		PA		29-11		27-41-12	D00698		8		D40222P	B01			YC051-YD153
0523	20		PA		30-0		27-41-12	D00698		8		D40222P	B01			YD154-YD158, YL951-YR328
0524	20		PA		29-11		27-41-12	D00698		1		D40222P	B02			YC051-YD153
0524	20		PA		30-0		27-41-12	D00698		1		D40222P	B02			YD154-YD158, YL951-YR328
0525	20		PA		12-8		27-41-12	D00698		2		D46150P		1		YC051-YC055
0525	20		PA		12-9		27-41-12	D00698		2		D46150P		1		YC056-YD158, YL951-YR328
0526	20		PA		29-11		27-41-12	D00698		10		D40222P	B09			YC051-YD153
0526	20		PA		30-0		27-41-12	D00698		10		D40222P	B09			YD154-YD158, YL951-YR328
0527	20		PA		3-4		27-41-11	D00698		3		GD00809	DC..	1A		YC051-YD153
0527	20		PA		2-7		27-41-11	D00698		3		GD00809	DC..	1A		YD154-YD158, YL951-YR328
0528	20		PA		3-4		27-41-11	D00698		4		GD00809	DC..	1A		YC051-YD153
0528	20		PA		2-7		27-41-11	D00698		4		GD00809	DC..	1A		YD154-YD158, YL951-YR328
0529	24		PK		30-5		27-11-11	D02930		9		D40222P	B15			YD154-YD158, YL951-YR328
0530	20		PA		30-2		27-41-11	TB0806Z	B017	1A		D40222P	B03			YC051-YC052
0530	20		PA		29-11		27-41-11	TB0806Z	B017	1A		D40222P	B03			YC053-YC055
0530	20		PA		30-0		27-41-11	TB0806Z	B017	1A		D40222P	B03			YC056-YD158, YL951-YR328
0531	20		PA		30-2		27-41-11	TB0806Z	A021	1A		D40222P	B04			YC051-YC052
0531	20		PA		30-0		27-41-11	TB0806Z	A021	1A		D40222P	B04			YC053-YD158, YL951-YR328
0532	24		PK		14-9		27-11-11	D40820P		6		D02930		10		YC051-YD158, YL951-YR328
0534	24		PK		14-0		27-28-11	D02934		3		D40818P	A08			YC051-YD158, YL951-YR328
0536	22		GK		21-1		27-54-11	D05150P		9		D40820P		9		YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W6200

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6208	286A6208			P8 TO MISC EQUIPMENT (continued)											
0541	22		PA		36-8	27-54-11	D05150P	11			D40222P	B20			YC051-YD158, YL951-YR328
0543	20		PA		14-8	27-41-11	D40820P	16			TB0806Y	A009	1A		YC051-YC052
0543	20		PA		14-5	27-41-11	D40820P	16			TB0806Y	A009	1A		YC053-YD158, YL951-YR328
0549	22		PA		19-4	32-64-21	D05148P	5			D46150P	24			YC051-YC055
0549	22		PA		19-5	32-64-21	D05148P	5			D46150P	24			YC056-YD158, YL951-YR328
0555	20		PA		1-11	27-62-11	D01084	1			GD01044	DC..	E		YC051-YD158, YL951-YR328
0557	20		PA		1-11	27-62-11	D01084	6			GD01044	DC..	E		YC051-YC055
0557	20		PA		1-6	27-62-11	D01084	6			GD01044	DC..	E		YC056-YD158, YL951-YR328
0558	20		PA		37-10	27-62-11	D01084	5			D40222P	A09			YC051-YC055
0558	20		PA		38-1	27-62-11	D01084	5			D40222P	A09			YC056-YD158, YL951-YR328
0561	22		PA		16-11	27-62-21	D46110P	A03			D05148P	12			YC051-YD158, YL951-YR328
0562	22		PA		16-11	31-53-11	D05148P	10			D46110P	A05			YC051-YD158, YL951-YR328
0563	20		PA		2-3	31-53-11	D05148P	11			GD00800	DC..	1A		YC051-YD158, YL951-YR328
0564	20		PA		4-2	27-11-11	D02930	8			GD00811	AC..	1A		YC051-YD158, YL951-YR328
0566	20		PA		30-6	27-23-11	D40528J	3			D40222P	A12			YC051-YD158, YL951-YR328
0567	20		PA		30-6	27-23-11	D40528J	4			D40222P	A13			YC051-YD158, YL951-YR328
0568	20		PA		30-6	27-23-11	D40528J	5			D40222P	A14			YC051-YD158, YL951-YR328
0571	22		PA		30-6	29-11-11	D40528J	14			D40222P	A17			YC051-YD158, YL951-YR328
0574	22		PA		13-7	32-31-11	D40820P	19			D40818P	A05			YC051-YD158, YL951-YR328
0575	22		PA		13-7	32-64-11	D40820P	18			D40818P	A06			YC051-YD158, YL951-YR328
0576	20		PA		5-4	27-62-21	D10199	10			GD00800	DC..	1A		YC051-YC055
0576	20		PA		5-5	27-62-21	D10199	10			GD00800	DC..	1A		YC056-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W6200

Page 15

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W6208	286A6208				P8 TO MISC EQUIPMENT (continued)											
0577	22		PA		18-0	27-62-21		D10199				D46110P	B03			YC051-YC055
0577	22		PA		18-1	27-62-21		D10199				D46110P	B03			YC056-YD158, YL951-YR328
0581	22		PA		18-0	32-42-11		D10199				D46110P	A04			YC051-YC055
0581	22		PA		18-1	32-42-11		D10199				D46110P	A04			YC056-YD158, YL951-YR328
0582	22		PA		18-0	32-42-11		D10199				D46110P	B04			YC051-YC055
0582	22		PA		18-1	32-42-11		D10199				D46110P	B04			YC056-YD158, YL951-YR328
0583	22		PA		9-3	29-23-11		D40820P				D46110P	B02			YC051-YD158, YL951-YR328
0584	22		PA		9-3	29-25-11		D40820P				D46110P	A01			YC051-YD158, YL951-YR328
0585	22		PA		9-3	29-25-11		D40820P				D46110P	B01			YC051-YD158, YL951-YR328
0586	20		PA		36-9	27-81-51		D05150P				D40228P	A01			YC051-YD158, YL951-YR328
0587	20		PA		36-9	27-81-51		D05150P				D40228P	B01			YC051-YD158, YL951-YR328
0595	22		PA		9-3	MULTI		D40820P				D46110P	A07			YL951-YL954
0595	22		PA		9-3	SPARE		D40820P				D46110P	A07			YL955-YL999, YN236-YN260
0595	22		PA		9-3	46-11-51		D40820P				D46110P	A07			YN231-YN235
0608	20		PA		11-9	27-41-11		D03124				TB0806Z	B017	1A		YC051-YC052
0608	20		PA		11-6	27-41-11		D03124				TB0806Z	B017	1A		YC053-YD158, YL951-YR328
0609	20		PA		11-6	27-41-11		D03124				TB0803Y	B011	1A		YC051-YD158, YL951-YR328
0610	20		PA		11-6	27-41-11		D03124				TB0803Y	A011	1A		YC051-YD158, YL951-YR328
0611	20		PA		11-9	27-41-11		D03124				TB0806Z	A021	1A		YC051-YC052
0611	20		PA		11-6	27-41-11		D03124				TB0806Z	A021	1A		YC053-YD158, YL951-YR328
0612	20		PA		11-6	27-41-11		D03124				TB0803Y	B009	1A		YC051-YD158, YL951-YR328
0613	20		PA		11-9	27-41-11		D03124				TB0806Z	A017	1A		YC051-YC052
0613	20		PA		11-6	27-41-11		D03124				TB0806Z	A017	1A		YC053-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W6200

Page 16

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6208	286A6208			P8 TO MISC EQUIPMENT (continued)											
0614	20		PA		3-1	27-41-11	D03124		7		GD00802	DC..	1		YC051-YD158, YL951-YR328
0615	20		PA		3-1	27-41-11	D03124		2		GD00802	DC..	1		YC051-YD158, YL951-YR328
0618	20		PA		30-6	27-23-11	D40528J		18		D40222P	B13			YC051-YD158, YL951-YR328
0620	20		PA		30-6	27-23-11	D40528J		17		D40222P	B12			YC051-YD158, YL951-YR328
0623	20		PA		2-3	32-64-21	D05148P		6		GD00800	DC..	1A		YC051-YD158, YL951-YR328
0624	20		PA		3-0	27-41-11	D12156		6		TB0806Z	B017	1A		YC051-YC052
0624	20		PA		2-9	27-41-11	D12156		6		TB0806Z	B017	1A		YC053-YD158, YL951-YR328
0625	20		PA		4-7	27-41-11	D12156		12		TB0803Y	B009	1A		YC051-YD158, YL951-YR328
0626	20		PA		4-7	27-41-11	D12156		3		TB0803Y	A011	1A		YC051-YD158, YL951-YR328
0627	20		PA		2-11	27-41-11	D12156		5		TB0806Z	A021	1A		YC051-YC052
0627	20		PA		2-9	27-41-11	D12156		5		TB0806Z	A021	1A		YC053-YD158, YL951-YR328
0628	20		PA		4-7	27-41-11	D12156		10		TB0803Y	B011	1A		YC051-YD158, YL951-YR328
0629	20		PA		3-0	27-41-11	D12156		8		TB0806Z	A017	1A		YC051-YC052
0629	20		PA		2-9	27-41-11	D12156		8		TB0806Z	A017	1A		YC053-YD158, YL951-YR328
0630	20		PA		4-2	27-41-11	D12156		7		GD00803	DC..	1A		YC051-YD158, YL951-YR328
0631	20		PA		4-2	27-41-11	D12156		2		GD00803	DC..	1A		YC051-YD158, YL951-YR328
0641	20		PA		11-8	73-22-11	D40820P		17		D46150P		8		YC051-YC055
0641	20		PA		11-9	73-22-11	D40820P		17		D46150P		8		YC056-YD158, YL951-YR328
0642	24		PK		11-8	73-22-31	D40820P		1		D46150P		9		YC051-YC055
0642	24		PK		11-9	73-22-31	D40820P		1		D46150P		9		YC056-YD158, YL951-YR328
0643	20		PA		11-8	74-11-11	D40820P		3		D46150P		10		YC051-YC055
0643	20		PA		11-9	74-11-11	D40820P		3		D46150P		10		YC056-YD158, YL951-YR328
0644	24		PK		11-8	76-21-21	D40820P		14		D46150P		13		YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W6200

Page 17

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6208	286A6208				P8 TO MISC EQUIPMENT (continued)											
0644	24		PK		11-9	76-21-21	D40820P		14			D46150P		13		YC056-YD158, YL951-YR328
0712	20		PA		9-3	SPARE	D40820P		11			D46110P		A02		YC051-YD158
0712	20		PA		9-3	33-45-11	D40820P		11			D46110P		A02		YL951-YR328
1101	20		X1	BN	27-4	27-62-11	D40222P		A08			D46150P		2		YC051-YC055
1101	20		X1	BN	27-5	27-62-11	D40222P		A08			D46150P		2		YC056-YD158, YL951-YR328
1101Z				BN	0-0	27-62-11	D40222P		A07			D46150P		3		YC051-YD158, YL951-YR328
1102	20		X1	BP	20-7	27-62-11	D01084		7			D46150P		4		YC051-YC055
1102	20		X1	BP	20-10	27-62-11	D01084		7			D46150P		4		YC056-YD158, YL951-YR328
1102Z				BP	0-0	27-62-11	D01084		DED			D46150P		5		YC051-YD158, YL951-YR328
1103	20		X1	BQ	37-10	27-62-11	D01084		3			D40222P		B08		YC051-YD158, YL951-YR328
1103Z				BQ	0-0	27-62-11	D01084		DED			D40222P		B07		YC051-YD158, YL951-YR328
1104	20		X1	BR	3-4	27-62-11	D05148P		9			SM00002		9		YC051-YC055
1104	20		X1	BR	4-7	27-62-11	D05148P		9			SM00002		9		YC056-YD158, YL951-YR328
1104Z				BR	0-0	27-62-11	D05148P		DED			SM00REF		2		YC051-YD158, YL951-YR328
1105	20		X1	BS	3-6	27-62-11	D10199		5			SM00002		9		YC051-YD153
1105	20		X1	BS	2-4	27-62-11	D10199		5			SM00002		9		YD154-YD158, YL951-YR328
1105Z				BS	0-0	27-62-11	D10199		DED			SM00REF		2		YC051-YD158, YL951-YR328
1106	20		X1	BT	27-4	27-62-11	D40222P		A10			D46150P		6		YC051-YC055
1106	20		X1	BT	27-5	27-62-11	D40222P		A10			D46150P		6		YC056-YD158, YL951-YR328
1106Z				BT	0-0	27-62-11	D40222P		B10			D46150P		7		YC051-YD158, YL951-YR328
1107	20		X1	BU	17-6	27-62-11	SM00002			9		D46150P		11		YC051-YC055
1107	20		X1	BU	18-9	27-62-11	SM00002			9		D46150P		11		YC056-YD158, YL951-YR328
1107Z				BU	0-0	27-62-11	SM00REF		2			D46150P		12		YC051-YD158, YL951-YR328
1108	20		X1	BV	34-9	27-62-11	D40222P		B05			SM00001		9		YC051-YC055

WIRE LIST
D280A108

91-21-11
Section W6200
Page 18
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W6208	286A6208	P8 TO MISC EQUIPMENT (continued)													
1108	20	X1	BV	36-0	27-62-11	D40222P	B05		SM00001		9		YC056-YD158, YL951-YR328		
1108Z			BV	0-0	27-62-11	D40222P	B06		SM00REF		1		YC051-YD158, YL951-YR328		
1109	20	X1	BW	11-8	27-62-11	D40820P	15		D46150P		25		YC051-YC055		
1109	20	X1	BW	11-9	27-62-11	D40820P	15		D46150P		25		YC056-YD158, YL951-YR328		
1109Z			BW	0-0	27-62-11	D40820P	DED		D46150P		26		YC051-YD158, YL951-YR328		
1110	20	X1	BX	17-6	27-62-11	SM00001		9	D46150P		27		YC051-YC055		
1110	20	X1	BX	18-9	27-62-11	SM00001		9	D46150P		27		YC056-YD158, YL951-YR328		
1110Z			BX	0-0	27-62-11	SM00REF		1	D46150P		28		YC051-YD158, YL951-YR328		
1111	20	X1	BY	3-4	27-62-11	D05148P		8	SM00001		9		YC051-YC055		
1111	20	X1	BY	4-7	27-62-11	D05148P		8	SM00001		9		YC056-YD158, YL951-YR328		
1111Z			BY	0-0	27-62-11	D05148P	DED		SM00REF		1		YC051-YD158, YL951-YR328		
1112	20	X1	BZ	3-6	27-62-11	D10199		7	SM00001		9		YC051-YC055		
1112	20	X1	BZ	2-4	27-62-11	D10199		7	SM00001		9		YC056-YD158, YL951-YR328		
1112Z			BZ	0-0	27-62-11	D10199	DED		SM00REF		1		YC051-YD158, YL951-YR328		
2001B	22	PB	GA	13-3	27-51-11	D10537		1	D40818P		B01		YC051-YD158, YL951-YR328		
2001R	22	PB	GA	0-0	27-51-11	D10537		5	D40818P		A01		YC051-YD158, YL951-YR328		
2201B	24	PL	KA	14-0	27-28-11	D02934		10	D40818P		A07		YC051-YD158, YL951-YR328		
2201R	24	PL	KA	0-0	27-28-11	D02934		9	D40818P		B08		YC051-YD158, YL951-YR328		
3001B	22	PC	WA	13-3	27-51-11	D10537		2	D40818P		B02		YC051-YD158, YL951-YR328		
3001R	22	PC	WA	0-0	27-51-11	D10537		3	D40818P		A02		YC051-YD158, YL951-YR328		
3001Y	22	PC	WA	0-0	27-51-11	D10537		4	D40818P		B03		YC051-YD158, YL951-YR328		

WIRE LIST

D280A108

91-21-11

Section W6200

Page 19

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W6208	286A6208				P8 TO MISC EQUIPMENT (continued)												
5501	20		PA		4-3	33-11-41	D02934				1		TB0801W	B013	1		YC051-YD158, YL951-YR328
5502	20		PA		4-2	33-11-41	D02934				2		GD00805	AC..	1A		YC051-YD158, YL951-YR328
5503	20		PA		4-1	33-11-41	D02930				5		TB0801W	B013	1		YC051-YD158, YL951-YR328
5504	20		PA		3-11	33-11-41	D02930				6		GD00805	AC..	1A		YC051-YD158, YL951-YR328
5505	16		PA		12-4	33-11-41	D05148P				4		TB0801W	B005	1		YC051-YD158, YL951-YR328
5506	16		PA		2-2	33-11-41	D05148P				7		GD00802	AC..	1		YC051-YD158, YL951-YR328
5507	20		CQ		2-3	33-18-61	D05148P				3		GD00800	DC..	1A		YC051-YD158, YL951-YR328
5508	20		CQ		12-8	33-18-61	D05148P				1		TB0803Z	A005	1A		YC051-YD158, YL951-YR328
5509	20		CQ		12-9	33-18-61	D05148P				2		TB0803X	A002	1A		YC051-YD158, YL951-YR328
5510	22		PA		12-4	23-43-11	D40818P		A10				TB0606X	B003	1A		YC051-YD158, YL951-YR328

WIRE LIST
D280A108

91-21-11
Section W6200
Page 20 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6210		286A6210				P92 (AFT DISC) TO E/E BAY										
0214		20		PA		20-0	28-23-11	R00963	X1	D		D40938P	A06			YD160-YR328
0215		20		PA		20-0	28-23-11	R00963	X2	D		D40938P	A07			YD160-YR328
0504		18		GK		2-6	24-32-11	D11738	27			D40370P	F			ALL
0505		18		GK		2-6	24-32-11	D11738	29			D40370P	G			ALL
0506		18		GK		2-6	24-32-11	D11738	28			D40370P	H			ALL
0510		22		PA		12-7	29-11-11	D40370P	A05			D40372P	2			YC051-YC055
0510		22		PA		12-10	29-11-11	D40370P	A05			D40372P	2			YC056-YR328
0514		24		B6		15-4	24-31-11	TB5801X	A001	1A		D00042	8			YC051-YC058
0514		24		B6		3-10	24-31-11	TB5801X	A001	1A		D00042	8			YC059-YD158
0514		24		B6		3-5	24-31-11	TB5801X	A001	1A		D00042	8			YD160-YR328
0515		20		PA		12-7	24-22-31	D11738	23			D40372P	4			YC051-YC055
0515		20		PA		12-10	24-22-31	D11738	23			D40372P	4			YC056-YR328
0516		20		PA		2-7	28-23-11	D11738	26			D40938P	B06			ALL
0517		20		PA		2-7	28-23-11	D11738	7			D40938P	B07			ALL
0518		20		PA		2-7	28-23-11	D11738	10			D40938P	B08			ALL
0519		24		B6		15-4	24-31-11	TB5801X	A002	1A		D00042	9			YC051-YC058
0519		24		B6		3-10	24-31-11	TB5801X	A002	1A		D00042	9			YC059-YD158
0519		24		B6		3-5	24-31-11	TB5801X	A002	1A		D00042	9			YD160-YR328
0520		24		B6		0-7	24-31-11	D00042	5			D00042	6			ALL
0521		20		CQ		7-5	24-31-11	D00042	2			GD03200	ST..	1A		YC051-YC058
0521		20		CQ		7-9	24-31-11	D00042	2			GD03200	ST..	1A		YC059-YD158
0521		20		CQ		6-10	24-31-11	D00042	2			GD03200	ST..	1A		YD160-YR328
0522		24		B6		11-3	24-31-11	D02936	11			D00042	11			YC051-YC058
0522		24		B6		10-11	24-31-11	D02936	11			D00042	11			YC059-YD158
0522		24		B6		10-5	24-31-11	D02936	11			D00042	11			YD160-YR328
0523		24		B6		11-3	24-31-11	D02936	12			D00042	12			YC051-YC058
0523		24		B6		10-11	24-31-11	D02936	12			D00042	12			YC059-YD158
0523		24		B6		10-5	24-31-11	D02936	12			D00042	12			YD160-YR328
0524		24		B6		11-3	24-31-11	D02936	1			D00042	1			YC051-YC058
0524		24		B6		10-11	24-31-11	D02936	1			D00042	1			YC059-YD158
0524		24		B6		10-5	24-31-11	D02936	1			D00042	1			YD160-YR328
0525		24		B6		11-3	24-31-11	D02936	3			D00042	3			YC051-YC058
0525		24		B6		10-11	24-31-11	D02936	3			D00042	3			YC059-YD158
0525		24		B6		10-5	24-31-11	D02936	3			D00042	3			YD160-YR328
0530		18		CQ		4-10	24-53-11	D11738	30			T00006	HV	E		ALL
1101		18		X1	BN	2-3	24-32-11	D11456	G			D40370P	J			ALL
1101Z					BN	0-0	24-32-11	D11456	DED			D40370P	DED			ALL
1102		18		X1	BP	2-3	24-32-11	D11456	H			D40370P	K			ALL
1102Z					BP	0-0	24-32-11	D11456	DED			D40370P	DED			ALL

WIRE LIST

D280A108

91-21-11

Section W6210

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6210	286A6210				P92 (AFT DISC) TO E/E BAY (continued)											
1103	18	X1	BO		2-4	24-32-11		D11456		I		D40938P		F		ALL
1103Z			BO		0-0	24-32-11		D11456		DED		D40938P		DED		ALL
2201B	22	X2	KA		4-6	24-23-21		D40938P		B02		GD00272		ST..	E	ALL
2201R	22	X2	KA		0-0	24-23-21		D40938P		A02		D11738		20		ALL
2201Z			KA		0-0	24-23-21		D40938P		DED		D11738		DED		ALL
2202B	22	X2	KB		4-3	24-41-11		D40938P		B01		GD03404		ST..	1	ALL
2202R	22	X2	KB		0-0	24-41-11		D40938P		A01		D11738		21		ALL
2202Z			KB		0-0	24-41-11		D40938P		DED		D11738		DED		ALL
3201B	20	PC	YA		2-7	28-23-11		D11738		14		D40938P		A05		ALL
3201R	20	PC	YA		0-0	28-23-11		D11738		12		D40938P		A03		ALL
3201Y	20	PC	YA		0-0	28-23-11		D11738		13		D40938P		A04		ALL
3202B	18	PC	YB		2-7	28-23-11		D11738		33		D40938P		J		YC051-YD158
3202B	18	PC	YB		20-0	28-23-11		D11738		33		R00963		C2	E	YD160-YR328
3202R	18	PC	YB		0-0	28-23-11		D11738		31		D40938P		G		YC051-YD158
3202R	18	PC	YB		0-0	28-23-11		D11738		31		R00963		A2	E	YD160-YR328
3202Y	18	PC	YB		0-0	28-23-11		D11738		32		D40938P		H		YC051-YD158
3202Y	18	PC	YB		0-0	28-23-11		D11738		32		R00963		B2	E	YD160-YR328
3203B	20	PC	YC		2-7	28-23-11		D11738		3		D40938P		B05		ALL
3203R	20	PC	YC		0-0	28-23-11		D11738		11		D40938P		B03		ALL
3203Y	20	PC	YC		0-0	28-23-11		D11738		2		D40938P		B04		ALL
3204B	20	PC	YD		16-2	24-31-11		D00042		7		D11738		17		YC051-YC055, YD160-YR328
3204B	20	PC	YD		16-1	24-31-11		D00042		7		D11738		17		YC056-YC058
3204B	20	PC	YD		16-5	24-31-11		D00042		7		D11738		17		YC059-YD158
3204R	20	PC	YD		0-0	24-31-11		D00042		4		D11738		18		ALL
3204Y	20	PC	YD		0-0	24-31-11		D00042		10		D11738		16		ALL
3205B	18	PC	YE		20-0	28-23-11		R00963		C1	E	D40938P		J		YD160-YR328
3205R	18	PC	YE		0-0	28-23-11		R00963		A1	E	D40938P		G		YD160-YR328
3205Y	18	PC	YE		0-0	28-23-11		R00963		B1	E	D40938P		H		YD160-YR328
4101B	20	PD	N6		4-3	24-21-21		D40370P		B01		D11738		37		ALL
4101G	20	PD	N6		0-0	24-21-21		D40370P		A02		GD03404		AC..	1	ALL
4101R	20	PD	N6		0-0	24-21-21		D40370P		A01		D11738		35		ALL
4101Y	20	PD	N6		0-0	24-21-21		D40370P		B02		D11738		36		ALL
4102B	22	PD	P6		4-3	24-41-11		D40370P		B03		D11738		6		ALL
4102G	22	PD	P6		0-0	24-41-11		D40370P		A04		GD03404		ST..	1	ALL
4102R	22	PD	P6		0-0	24-41-11		D40370P		A03		D11738		4		ALL
4102Y	22	PD	P6		0-0	24-41-11		D40370P		B04		D11738		5		ALL
5510	22	PA			12-7	21-27-21		D11738		25		D40372P		8		YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W6210

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6210		286A6210			P92 (AFT DISC) TO E/E BAY (continued)											
5510		22		PA		12-10	21-27-21	D11738	25			D40372P	8			YC056-YC059, YC065-YR328 YC060-YC064
5511		22		PA		12-10	21-27-21	D11738	25			SP00471	9			
W6212		286A6212			J39 (B) TO MISC EQUIPMENT											
0003		20		PA		29-0	44-21-10	D40708P	5			SP00823	9			YN501-YR328
0007		24		PK		34-8	23-42-14	D43924P	B03			D40708P	12			YN501-YR328
0010		20		CQ		29-0	44-21-10	D40708P	17			SP00825	9			YN501-YR328
2001B		24		Y2	GA	34-8	23-42-14	D43924P	B01			D40708P	6			YN501-YR328
2001R		24		Y2	GA	0-0	23-42-14	D43924P	A01			D40708P	1			YN501-YR328
2001Z					GA	0-0	23-42-14	D43924P			AB	D40708P			AA	YN501-YR328
2002B		24		Y2	GB	34-8	23-42-14	D43924P	B02			D40708P	11			YN501-YR328
2002R		24		Y2	GB	0-0	23-42-14	D43924P	A02			D40708P	4			YN501-YR328
2002Z					GB	0-0	23-42-14	D43924P			AB	D40708P			AA	YN501-YR328
FRAA						0-0	23-42-14	D40708P			AA	D40708P	21			YN501-YR328
FRAB						0-0	23-42-14	D43924P			AB	D43924P	PERG	1F		YN501-YR328
W6214		286A6214			P6A TO E2-2, E4-1 (LA2)											
0001		20		PA		29-9	33-32-11	D40380P	A20			D40444P	19			YC051-YC052
0001		20		PA		29-10	33-32-11	D40380P	A20			D40444P	19			YC053-YC055
0001		20		PA		30-8	33-32-11	D40380P	A20			D40444P	19			YC056-YR323, YR325-YR328
0002		20		PA		29-9	33-32-11	D40380P	B20			D40444P	20			YC051-YC052
0002		20		PA		29-10	33-32-11	D40380P	B20			D40444P	20			YC053-YC055
0002		20		PA		30-8	33-32-11	D40380P	B20			D40444P	20			YC056-YR323, YR325-YR328
0030		22		PA		10-8	23-22-11	D41012P	A01			D40328P	B06			YC051-YC055
0030		22		PA		11-8	23-22-11	D41012P	A01			D40328P	B06			YC056-YR323, YR325-YR328
0031		22		PA		10-8	23-22-11	D41012P	A02			D40328P	B07			YC051-YC055
0031		22		PA		11-8	23-22-11	D41012P	A02			D40328P	B07			YC056-YR323, YR325-YR328
0032		22		PA		10-8	23-22-11	D41012P	A03			D40328P	B08			YC051-YC055
0032		22		PA		11-8	23-22-11	D41012P	A03			D40328P	B08			YC056-YR323, YR325-YR328
0033		22		PA		10-8	23-71-01	D41012P	A04			D40328P	B04			YC051-YC055
0033		22		PA		11-8	23-71-01	D41012P	A04			D40328P	B04			YC056-YR323, YR325-YR328
0034		22		PA		10-8	23-71-01	D41012P	A05			D40328P	B05			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W6210

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6214	286A6214				P6A TO E2-2, E4-1 (LA2) (continued)										
0034	22		PA		11-8	23-71-01	D41012P	A05			D40328P	B05			YC056-YR323, YR325-YR328
0201	22		CQ		35-0	23-51-51	D40444P	23			D40378P	A01			YC051-YC052
0201	22		CQ		35-1	23-51-51	D40444P	23			D40378P	A01			YC053-YC055
0201	22		CQ		35-10	23-51-51	D40444P	23			D40378P	A01			YC056-YR323, YR325-YR328
0202	22		CQ		35-0	23-51-51	D40444P	24			D40378P	B10			YC051-YC052
0202	22		CQ		35-1	23-51-51	D40444P	24			D40378P	B10			YC053-YC055
0202	22		CQ		35-10	23-51-51	D40444P	24			D40378P	B10			YC056-YR323, YR325-YR328
0203	24		PK		22-8	21-31-24	D40380P	B04			D40774P	A01			YD158-YR323, YR325-YR328
0204	24		B6		22-8	21-31-24	D40380P	B05			D40774P	A10			YD158-YR323, YR325-YR328
0205	24		B6		22-8	21-31-24	D40380P	B08			D40774P	B01			YD158-YR323, YR325-YR328
0206	24		B6		22-8	21-31-24	D40380P	B09			D40774P	B10			YD158-YR323, YR325-YR328
0207	24		PK		22-8	21-31-24	D40380P	B07			D40774P	A03			YD158-YR323, YR325-YR328
0208	24		PK		22-8	21-31-24	D40380P	B06			D40774P	B03			YD158-YR323, YR325-YR328
0209	24		PK		22-8	21-31-24	D40380P	B02			D40774P	A04			YD158-YR323, YR325-YR328
0210	24		PK		22-8	21-31-24	D40380P	B03			D40774P	B04			YD158-YR323, YR325-YR328
0211	24		PK		22-8	21-31-24	D40380P	B10			D40774P	A02			YD158-YR323, YR325-YR328
0212	24		B6		23-0	21-31-23	D41012P	A08			D40774P	A09			YD158-YR323, YR325-YR328
0301	24		PK		32-11	21-51-12	D40444P	13			D41828P	A01			YC051-YC052
0301	24		PK		33-0	21-51-12	D40444P	13			D41828P	A01			YC053-YC055
0301	24		PK		34-8	21-51-12	D40444P	13			D41828P	A01			YC056-YL999, YR301-YR323, YR325-YR328
0302	24		PK		32-7	21-51-12	D40444P	17			D41814P	A01			YC051-YC052
0302	24		PK		32-8	21-51-12	D40444P	17			D41814P	A01			YC053-YC055

WIRE LIST

D280A108

91-21-11
Section W6210
Page 4
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W6214	286A6214				P6A TO E2-2, E4-1 (LA2) (continued)											
0302	24		PK		33-3	21-51-12	D40444P		17			D41814P	A01			YC056-YL999, YR301-YR323, YR325-YR328
0303	24		PK		32-7	21-51-12	D40444P		18			D41814P	B01			YC051-YC052
0303	24		PK		32-8	21-51-12	D40444P		18			D41814P	B01			YC053-YC055
0303	24		PK		33-3	21-51-12	D40444P		18			D41814P	B01			YC056-YL999, YR301-YR323, YR325-YR328
0310	24		PK		34-8	21-51-12	D40444P		16			D41828P	A03			YC065-YL999, YR301-YR323, YR325-YR328
1301R	20		X5	EN	10-8	26-11-21	D41012P		A06			D40328P	A10			YC051-YC055
1301R	20		X5	EN	11-8	26-11-21	D41012P		A06			D40328P	A10			YC056-YR323, YR325-YR328
1301Z				EN	0-0	26-11-21	D41012P		DED			D40328P	DED			YC051-YR323, YR325-YR328
1302R	20		X5	EP	10-8	26-11-21	D41012P		A07			D40328P	B10			YC051-YC055
1302R	20		X5	EP	11-8	26-11-21	D41012P		A07			D40328P	B10			YC056-YR323, YR325-YR328
1302Z				EP	0-0	26-11-21	D41012P		DED			D40328P	DED			YC051-YR323, YR325-YR328
1303R	20		X5	EQ	11-5	26-11-21	D40380P		B12			D40378P	B12			YC051-YC055
1303R	20		X5	EQ	12-0	26-11-21	D40380P		B12			D40378P	B12			YC056-YR323, YR325-YR328
1303Z				EQ	0-0	26-11-21	D40380P		DED			D40378P	DED			YC051-YR323, YR325-YR328
1304R	20		X5	ER	11-5	26-11-21	D40380P		B13			D40378P	B13			YC051-YC055
1304R	20		X5	ER	12-0	26-11-21	D40380P		B13			D40378P	B13			YC056-YR323, YR325-YR328
1304Z				ER	0-0	26-11-21	D40380P		DED			D40378P	DED			YC051-YR323, YR325-YR328
2001B	24		Y2	GA	11-5	21-31-24	D40380P		A04			D40378P	A02			YC051-YC055
2001B	24		Y2	GA	12-0	21-31-24	D40380P		A04			D40378P	A02			YC056-YD157
2001R	24		Y2	GA	0-0	21-31-24	D40380P		A05			D40378P	A03			YC051-YD157
2001Z				GA	0-0	21-31-24	D40380P		PERG	1F		D40378P	PERG	1F		YC051-YD157
2002B	24		Y2	GB	11-5	21-31-24	D40380P		A06			D40378P	A04			YC051-YC055
2002B	24		Y2	GB	12-0	21-31-24	D40380P		A06			D40378P	A04			YC056-YD157
2002R	24		Y2	GB	0-0	21-31-24	D40380P		A07			D40378P	A05			YC051-YD157
2002Z				GB	0-0	21-31-24	D40380P		PERG	1F		D40378P	PERG	1F		YC051-YD157

WIRE LIST

D280A108

91-21-11

Section W6210

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6214	286A6214			P6A TO E2-2, E4-1 (LA2) (continued)											
2003B	24	Y2	GC		11-5	21-31-24	D40380P	A08			D40378P	A06			YC051-YC055
2003B	24	Y2	GC		12-0	21-31-24	D40380P	A08			D40378P	A06			YC056-YD157
2003R	24	Y2	GC		0-0	21-31-24	D40380P	A09			D40378P	A07			YC051-YD157
2003Z			GC		0-0	21-31-24	D40380P	PERG	1F		D40378P	PERG	1F		YC051-YD157
2004B	24	Y2	GD		11-5	21-31-24	D40380P	A02			D40378P	A08			YC051-YC055
2004B	24	Y2	GD		12-0	21-31-24	D40380P	A02			D40378P	A08			YC056-YD157
2004R	24	Y2	GD		0-0	21-31-24	D40380P	A03			D40378P	A09			YC051-YD157
2004Z			GD		0-0	21-31-24	D40380P	PERG	1F		D40378P	PERG	1F		YC051-YD157
2005B	20	PB	GE		17-2	21-61-11	D41814P	A03			D03884	2			YC051-YC055
2005B	20	PB	GE		18-1	21-61-11	D41814P	A03			D03884	2			YC056-YD158
2005B	20	PB	GE		18-4	21-61-11	D41814P	A03			D03884	2			YD160-YL999, YR301-YR323, YR325-YR328
2005R	20	PB	GE		0-0	21-61-11	D41814P	A02			D03884	1			YC051-YL999, YR301-YR323, YR325-YR328
2006B	20	PB	GF		15-9	21-61-12	D41814P	A05			D03882	2			YC051-YC055
2006B	20	PB	GF		16-8	21-61-12	D41814P	A05			D03882	2			YC056-YL999, YR301-YR323, YR325-YR328
2006R	20	PB	GF		0-0	21-61-12	D41814P	A04			D03882	1			YC051-YL999, YR301-YR323, YR325-YR328
2007B	24	Y2	GG		22-8	21-31-24	D40380P	A04			D40774P	B05			YD158-YR323, YR325-YR328
2007R	24	Y2	GG		0-0	21-31-24	D40380P	A05			D40774P	A05			YD158-YR323, YR325-YR328
2007Z			GG		0-0	21-31-24	D40380P	PERG	1F		D40774P	PERG	1F		YD158-YR323, YR325-YR328
2008B	24	Y2	GH		22-8	21-31-24	D40380P	A06			D40774P	B06			YD158-YR323, YR325-YR328
2008R	24	Y2	GH		0-0	21-31-24	D40380P	A07			D40774P	A06			YD158-YR323, YR325-YR328
2008Z			GH		0-0	21-31-24	D40380P	PERG	1F		D40774P	PERG	1F		YD158-YR323, YR325-YR328
2009B	24	Y2	GI		22-8	21-31-24	D40380P	A08			D40774P	B07			YD158-YR323, YR325-YR328
2009R	24	Y2	GI		0-0	21-31-24	D40380P	A09			D40774P	A07			YD158-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W6210

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice		
W6214	286A6214				P6A TO E2-2, E4-1 (LA2) (continued)											
2009Z				GI	0-0	21-31-24	D40380P	PERG	1F		D40774P	PERG	1F	YD158-YR323, YR325-YR328		
2010B	24	Y2		GJ	22-8	21-31-24	D40380P	A02			D40774P	B08		YD158-YR323, YR325-YR328		
2010R	24	Y2		GJ	0-0	21-31-24	D40380P	A03			D40774P	A08		YD158-YR323, YR325-YR328		
2010Z				GJ	0-0	21-31-24	D40380P	PERG	1F		D40774P	PERG	1F	YD158-YR323, YR325-YR328		
5501	22	PA			33-11	SPARE	D40444P		1		D40328P	A03		YC051-YC052		
5501	22	PA			34-0	SPARE	D40444P		1		D40328P	A03		YC053-YC055		
5501	22	PA			35-2	SPARE	D40444P		1		D40328P	A03		YC056-YD157		
5501	22	PA			35-2	34-24-15	D40444P		1		D40328P	A03		YD158		
5501	20	CQ			35-2	34-24-15	D40444P		1		D40328P	A03		YD160-YR323, YR325-YR328		
5502	24	PK			11-5	21-51-14	D40380P	A10			D40378P	A11		YC051-YC055		
5502	24	PK			12-0	21-51-14	D40380P	A10			D40378P	A11		YC056-YR323, YR325-YR328		
5503	24	B6			35-0	21-51-15	D40444P		21		D40378P	A12		YC051-YC052		
5503	24	B6			35-1	21-51-15	D40444P		21		D40378P	A12		YC053-YC055		
5503	24	B6			35-10	21-51-15	D40444P		21		D40378P	A12		YC056-YR323, YR325-YR328		
5504	24	PK			11-5	36-11-11	D40378P	A13			D40380P	A11		YC051-YC055		
5504	24	PK			12-0	36-11-11	D40378P	A13			D40380P	A11		YC056-YR323, YR325-YR328		
5505	24	PK			11-5	36-11-11	D40378P	A14			D40380P	A12		YC051-YC055		
5505	24	PK			12-0	36-11-11	D40378P	A14			D40380P	A12		YC056-YR323, YR325-YR328		
5506	24	PK			11-5	36-11-11	D40378P	A15			D40380P	A13		YC051-YC055		
5506	24	PK			12-0	36-11-11	D40378P	A15			D40380P	A13		YC056-YR323, YR325-YR328		
5507	24	PK			11-5	36-11-11	D40378P	A16			D40380P	A14		YC051-YC055		
5507	24	PK			12-0	36-11-11	D40378P	A16			D40380P	A14		YC056-YR323, YR325-YR328		
5511	24	PK			11-5	21-42-11	D40380P	A01			D40378P	A17		YC051-YC055		
5511	24	PK			12-0	21-42-11	D40380P	A01			D40378P	A17		YC056-YR323, YR325-YR328		
5512	24	PK			11-5	21-42-11	D40380P	B01			D40378P	A18		YC051-YC055		
5512	24	PK			12-0	21-42-11	D40380P	B01			D40378P	A18		YC056-YR323, YR325-YR328		

WIRE LIST

D280A108

91-21-11

Section W6210

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description			From				To				
	GA	CO	TY		FT-IN	Diagram		Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6214	286A6214				P6A TO E2-2, E4-1 (LA2) (continued)											
5513	24		PK		11-5	21-31-24		D40380P		B02		D40378P		A19		YC051-YC055
5513	24		PK		12-0	21-31-24		D40380P		B02		D40378P		A19		YC056-YD157
5514	24		PK		11-5	21-31-24		D40380P		B03		D40378P		A20		YC051-YC055
5514	24		PK		12-0	21-31-24		D40380P		B03		D40378P		A20		YC056-YD157
5515	24		PK		11-5	21-31-24		D40380P		B04		D40378P		B01		YC051-YC055
5515	24		PK		12-0	21-31-24		D40380P		B04		D40378P		B01		YC056-YD157
5516	24		B6		11-5	21-31-24		D40380P		B05		D40378P		B02		YC051-YC055
5516	24		B6		12-0	21-31-24		D40380P		B05		D40378P		B02		YC056-YD157
5517	24		PK		11-5	21-31-24		D40380P		B06		D40378P		B03		YC051-YC055
5517	24		PK		12-0	21-31-24		D40380P		B06		D40378P		B03		YC056-YD157
5518	24		PK		11-5	21-31-24		D40380P		B07		D40378P		B04		YC051-YC055
5518	24		PK		12-0	21-31-24		D40380P		B07		D40378P		B04		YC056-YD157
5519	24		PK		11-5	21-31-24		D40380P		B08		D40378P		B05		YC051-YC055
5519	24		PK		12-0	21-31-24		D40380P		B08		D40378P		B05		YC056-YD157
5520	24		PK		11-5	21-31-24		D40380P		B09		D40378P		B06		YC051-YC055
5520	24		PK		12-0	21-31-24		D40380P		B09		D40378P		B06		YC056-YD157
5521	24		PK		11-5	21-31-24		D40380P		B10		D40378P		B07		YC051-YC055
5521	24		PK		12-0	21-31-24		D40380P		B10		D40378P		B07		YC056-YD157
5522	22		PA		35-0	21-51-14		D40444P		22		D40378P		B09		YC051-YC052
5522	22		PA		35-1	21-51-14		D40444P		22		D40378P		B09		YC053-YC055
5522	22		PA		35-10	21-51-14		D40444P		22		D40378P		B09		YC056-YR323, YR325-YR328
5523	24		PK		33-11	21-51-14		D40444P		2		D40328P		A04		YC051-YC052
5523	24		PK		34-0	21-51-14		D40444P		2		D40328P		A04		YC053-YC055
5523	24		PK		35-2	21-51-14		D40444P		2		D40328P		A04		YC056-YR323, YR325-YR328
5524	24		PK		35-2	21-51-16		D40444P		3		D40328P		A05		YN231-YN501
5530	20		PA		20-1	21-61-21		D40328P		A06		D00512		3		YN231-YN501
5531	20		PA		20-1	21-61-21		D40328P		A07		D00512		1		YN231-YN501
5532	22		PA		18-7	21-61-21		D40328P		A08		D00514		1		YN231-YN501
5533	22		PA		18-7	21-61-21		D40328P		A09		D00514		2		YN231-YN501
5534	22		PA		19-4	21-61-21		D40378P		A10		D00514		3		YN231-YN501
5536	20		PA		11-5	SPARE		D40380P		B15		D40378P		B15		YC051-YC055
5536	20		PA		12-0	SPARE		D40380P		B15		D40378P		B15		YC056-YR323, YR325-YR328
5539	20		PA		11-5	30-71-11		D40380P		B19		D40378P		B18		YC051-YC055
5539	20		PA		12-0	30-71-11		D40380P		B19		D40378P		B18		YC056-YR323, YR325-YR328
5540	20		PA		35-0	SPARE		D40444P		9		D40378P		B16		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W6210

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6214		286A6214			P6A TO E2-2, E4-1 (LA2) (continued)											
5540		20		PA		35-1	SPARE	D40444P		9		D40378P		B16		YC053-YC055
5540		20		PA		35-10	SPARE	D40444P		9		D40378P		B16		YC056-YR323, YR325-YR328
5541		20		PA		35-0	SPARE	D40444P		10		D40378P		B14		YC051-YC052
5541		20		PA		35-1	SPARE	D40444P		10		D40378P		B14		YC053-YC055
5541		20		PA		35-10	SPARE	D40444P		10		D40378P		B14		YC056-YR323, YR325-YR328
5544		20		PA		33-11	SPARE	D40444P		4		D40328P		B02		YC051-YC052
5544		20		PA		34-0	SPARE	D40444P		4		D40328P		B02		YC053-YC055
5544		20		PA		35-2	SPARE	D40444P		4		D40328P		B02		YC056-YR323, YR325-YR328
5545		20		PA		33-11	SPARE	D40444P		5		D40328P		B03		YC051-YC052
5545		20		PA		34-0	SPARE	D40444P		5		D40328P		B03		YC053-YC055
5545		20		PA		35-2	SPARE	D40444P		5		D40328P		B03		YC056-YR323, YR325-YR328
5546		24		B6		10-8	21-31-23	D40328P		B09		D41012P		A08		YC051-YC055
5546		24		B6		11-8	21-31-23	D40328P		B09		D41012P		A08		YC056-YD157
5548		20		PA		19-4	21-61-21	D40378P		B17		D11360		1		YN231-YN501
5549		20		PA		12-2	21-61-21	D11360		2		GD00422		DC..	E	YN231-YN501
5550		24		PK		32-11	21-61-11	D40444P		3		D41828P		A02		YC051-YC052
5550		24		PK		33-0	21-61-11	D40444P		3		D41828P		A02		YC053-YC055
5550		24		PK		34-8	21-61-11	D40444P		3		D41828P		A02		YC056-YL999, YR301-YR323, YR325-YR328
5551		20		PA		17-1	21-61-11	D40328P		A02		D03892		1		YC051-YC055
5551		20		PA		18-7	21-61-11	D40328P		A02		D03892		1		YC056-YL999, YR301-YR323, YR325-YR328
5552		20		PA		6-10	21-61-11	D03892		2		GD03200		DC..	1A	YC051-YD158
5552		20		PA		6-9	21-61-11	D03892		2		GD03200		DC..	1A	YD160-YL999, YR301-YR323, YR325-YR328
5553		20		PA		18-8	21-61-51	D40328P		A09		D03924		B		YC051-YC055
5553		20		PA		20-2	21-61-51	D40328P		A09		D03924		B		YC056-YD158
5553		20		PA		20-4	21-61-51	D40328P		A09		D03924		B		YD160-YL999, YR301-YR323, YR325-YR328
5554		20		PA		6-3	21-61-51	D03924		A		GD03200		DC..	1A	YC051-YD158

WIRE LIST

D280A108

91-21-11

Section W6210

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6214	286A6214				P6A TO E2-2, E4-1 (LA2) (continued)										
5554	20		PA		6-8	21-61-51	D03924		A		GD03200	DC..	1A		YD160-YL999, YR301-YR323, YR325-YR328
5556	20		PA		11-5	30-71-11	D40380P		A19		D40378P	B19			YC051-YC055
5556	20		PA		12-0	30-71-11	D40380P		A19		D40378P	B19			YC056-YL999, YR301-YR323, YR325-YR328
5556	20		PA		12-0	30-71-11	D40378P		B19		D40380P	A19			YN231-YN501
6001	24		PK		11-5	73-22-31	D40380P		B11		D40378P	B11			YC051-YC055
6001	24		PK		12-0	73-22-31	D40380P		B11		D40378P	B11			YC056-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W6210

Page 10 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6220	286A6220			E3-3 TO E4-1 (SA2)											
0301	24		PK		13-8	21-51-12	D41804P	A01			D41802P	A01			YC051-YL999, YR301-YR323, YR325-YR328
0302	24		PK		13-8	21-51-12	D41804P	A02			D41802P	A02			YC051-YL999, YR301-YR323, YR325-YR328
0303	24		PK		13-8	21-51-12	D41804P	A03			D41802P	A03			YC051-YL999, YR301-YR323, YR325-YR328
0304	24		PK		13-8	21-51-14	D41804P	A04			D41802P	A04			YC051-YL999, YR301-YR323, YR325-YR328
0305	24		PK		13-8	21-51-14	D41804P	A05			D41802P	A05			YC051-YL999, YR301-YR323, YR325-YR328
0306	24		PK		13-8	21-51-14	D41804P	A06			D41802P	A06			YC051-YL999, YR301-YR323, YR325-YR328
0307	24		PK		13-8	21-51-14	D41804P	A07			D41802P	A07			YC051-YL999, YR301-YR323, YR325-YR328
0308	24		PK		13-8	21-51-14	D41804P	A08			D41802P	A08			YC051-YL999, YR301-YR323, YR325-YR328
0401	24		PK		13-8	21-61-11	D41804P	B01			D41802P	B01			YC051-YL999, YR301-YR323, YR325-YR328
0402	24		PK		13-8	21-61-11	D41804P	B02			D41802P	B02			YC051-YL999, YR301-YR323, YR325-YR328
0403	24		PK		13-8	21-61-11	D41804P	B03			D41802P	B03			YC051-YL999, YR301-YR323, YR325-YR328
0404	24		PK		13-8	21-61-11	D41804P	B04			D41802P	B04			YC051-YL999, YR301-YR323, YR325-YR328
0405	24		PK		13-8	21-61-11	D41804P	B05			D41802P	B05			YC051-YL999, YR301-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W6220

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W6220	286A6220				E3-3 TO E4-1 (SA2) (continued)												
0406	24		PK		13-8		21-61-12	D41804P		B06		D41802P		B06		YC051-YL999, YR301-YR323, YR325-YR328	
0407	24		PK		13-8		21-61-12	D41804P		B07		D41802P		B07		YC051-YL999, YR301-YR323, YR325-YR328	
0408	24		PK		13-8		21-61-12	D41804P		B08		D41802P		B08		YC051-YL999, YR301-YR323, YR325-YR328	
W6222	286A6222				J4 TO E/E BAY AND STAB TRIM ACTUATOR												
0501	20		HL		54-8		27-41-12	SP00158			9	D40250J		5		YC051-YC052	
0501	20		PA		46-11		27-41-12	D40836P		1		D40250J		5		YC053-YL999	
0501	20		PA		37-3		27-41-12	D40836P		1		D40250J		5		YN231-YN260	
0501	20		PA		37-10		27-41-12	D40836P		1		D43404J		5		YN501	
0501	20		PA		47-8		27-41-12	D40836P		1		D43404J		5		YR301-YR323, YR325-YR328	
0502	20		HL		54-8		27-41-12	SP00160			9	D40250J		4		YC051-YC052	
0502	20		PA		46-11		27-41-12	D40836P		2		D40250J		4		YC053-YL999	
0502	20		PA		37-3		27-41-12	D40836P		2		D40250J		4		YN231-YN260	
0502	20		PA		37-10		27-41-12	D40836P		2		D43404J		4		YN501	
0502	20		PA		47-8		27-41-12	D40836P		2		D43404J		4		YR301-YR323, YR325-YR328	
0503	20		HL		121-1		27-41-12	SP00156			9	D40742P		3		YC051-YC052	
0503	20		PA		114-0		27-41-12	D40836P		3		D40742P		3		YC053-YC055	
0503	20		PA		113-10		27-41-12	D40836P		3		D40742P		3		YC056-YC058	
0503	20		PA		46-11		27-41-12	D40836P		3		D40250J		8		YC059-YL999	
0503	20		PA		37-3		27-41-12	D40836P		3		D40250J		8		YN231-YN260	
0503	20		PA		37-10		27-41-12	D40836P		3		D43404J		8		YN501	
0503	20		PA		47-8		27-41-12	D40836P		3		D43404J		8		YR301-YR323, YR325-YR328	
0504	18		HL		62-8		27-41-12	D40250J		3		D00700		8		YC051-YC052	
0504	18		PA		46-11		27-41-12	D40250J		3		D40836P		5	18	YC053-YL999	
0504	18		PA		37-3		27-41-12	D40250J		3		D40836P		5	18	YN231-YN260	
0504	18		PA		37-10		27-41-12	D43404J		3		D40836P		5	18	YN501	
0504	18		PA		47-8		27-41-12	D43404J		3		D40836P		5	18	YR301-YR323, YR325-YR328	
0505	18		HL		17-7		27-41-12	SP00154			9	D00700		6		YC051-YC052	
0506	18		HL		17-7		27-41-12	SP00152			9	D00700		7		YC051-YC052	

WIRE LIST

D280A108

91-21-11

Section W6220

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice
W6222	286A6222				J4 TO E/E BAY AND STAB TRIM ACTUATOR (continued)										
0508	18		HL		5-5	27-41-12	GD00046	AC..	1		D00700	10		YC051-YC052	
0509	18		HL		5-5	27-41-12	GD00046	DC..	1		D00700	5		YC051-YC052	
0510	18		HL		5-5	27-41-12	D00700		4		GD00046	ST..	1	YC051-YC052	
0511	20		PA		72-0	27-41-12	D40742P		1		D40250J	1		YC051-YC052, YC056-YL999	
0511	20		PA		72-2	27-41-12	D40742P		1		D40250J	1		YC053-YC055	
0511	20		PA		61-8	27-41-12	D40742P		1		D40250J	1		YN231-YN260	
0511	20		PA		62-3	27-41-12	D40742P		1		D43404J	1		YN501	
0511	20		PA		72-8	27-41-12	D40742P		1		D43404J	1		YR301-YR323, YR325-YR328	
0512	20		PA		72-0	27-41-12	D40742P		2		D40250J	2		YC051-YC052, YC056-YL999	
0512	20		PA		72-2	27-41-12	D40742P		2		D40250J	2		YC053-YC055	
0512	20		PA		61-8	27-41-12	D40742P		2		D40250J	2		YN231-YN260	
0512	20		PA		62-3	27-41-12	D40742P		2		D43404J	2		YN501	
0512	20		PA		72-8	27-41-12	D40742P		2		D43404J	2		YR301-YR323, YR325-YR328	
0513	16		PA		78-4	27-53-12	D40614P		1		D40248J	2		YC051-YC052	
0513	16		PA		76-1	27-53-12	D40614P		1		D40248J	2		YC053-YC055	
0513	16		PA		76-0	27-53-12	D40614P		1		D40248J	2		YC056-YL999, YR301-YR323, YR325-YR328	
0513	16		PA		66-1	27-53-12	D40614P		1		D40248J	2		YN231-YN501	
0514	16		PA		78-4	27-53-12	D40614P		2		D40248J	3		YC051-YC052	
0514	16		PA		76-1	27-53-12	D40614P		2		D40248J	3		YC053-YC055	
0514	16		PA		76-0	27-53-12	D40614P		2		D40248J	3		YC056-YL999, YR301-YR323, YR325-YR328	
0514	16		PA		66-1	27-53-12	D40614P		2		D40248J	3		YN231-YN501	
0515	16		PA		78-4	27-53-12	D40614P		3		D40248J	4		YC051-YC052	
0515	16		PA		76-1	27-53-12	D40614P		3		D40248J	4		YC053-YC055	
0515	16		PA		76-0	27-53-12	D40614P		3		D40248J	4		YC056-YL999, YR301-YR323, YR325-YR328	
0515	16		PA		66-1	27-53-12	D40614P		3		D40248J	4		YN231-YN501	
0516	16		PA		9-10	27-53-12	D40574P		1		D40602P	1		YC051-YL999, YR301-YR323, YR325-YR328	
0516	16		PA		9-9	27-53-12	D40574P		1		D40602P	1		YN231-YN501	

WIRE LIST

D280A108

91-21-11

Section W6220

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6222	286A6222			J4 TO E/E BAY AND STAB TRIM ACTUATOR (continued)											
0517	16		PA		9-10	27-53-12	D40574P		2		D40602P		2		YC051-YL999, YR301-YR323, YR325-YR328
0517	16		PA		9-9	27-53-12	D40574P		2		D40602P		2		YN231-YN501
0518	16		PA		9-10	27-53-12	D40574P		3		D40602P		3		YC051-YL999, YR301-YR323, YR325-YR328
0518	16		PA		9-9	27-53-12	D40574P		3		D40602P		3		YN231-YN501
0528	20		PA		69-10	27-11-11	D40432P		A01		D40248J		1		YC051-YC052
0528	20		PA		70-0	27-11-11	D40432P		A01		D40248J		1		YC053-YC055
0528	20		PA		69-9	27-11-11	D40432P		A01		D40248J		1		YC056-YL999, YR301-YR323, YR325-YR328
0528	20		PA		59-10	27-11-11	D40432P		A01		D40248J		1		YN231-YN501
0529	20		PA		69-10	27-11-11	D40432P		A02		D40248J		6		YC051-YC052
0529	20		PA		70-0	27-11-11	D40432P		A02		D40248J		6		YC053-YC055
0529	20		PA		69-9	27-11-11	D40432P		A02		D40248J		6		YC056-YL999, YR301-YR323, YR325-YR328
0529	20		PA		59-10	27-11-11	D40432P		A02		D40248J		6		YN231-YN501
0530	20		PA		69-10	27-11-11	D40432P		A03		D40248J		5		YC051-YC052
0530	20		PA		70-0	27-11-11	D40432P		A03		D40248J		5		YC053-YC055
0530	20		PA		69-9	27-11-11	D40432P		A03		D40248J		5		YC056-YL999, YR301-YR323, YR325-YR328
0530	20		PA		59-10	27-11-11	D40432P		A03		D40248J		5		YN231-YN501
0534	20		PA		77-5	27-41-12	D40616P		4		D40250J		6		YC059-YL999
0534	20		PA		67-2	27-41-12	D40616P		4		D40250J		6		YN231-YN260
0534	20		PA		67-9	27-41-12	D40616P		4		D43404J		6		YN501
0534	20		PA		78-2	27-41-12	D40616P		4		D43404J		6		YR301-YR323, YR325-YR328
0535	20		PA		72-0	27-41-12	D40742P		3		D40250J		7		YC059-YL999
0535	20		PA		61-8	27-41-12	D40742P		3		D40250J		7		YN231-YN260
0535	20		PA		62-3	27-41-12	D40742P		3		D43404J		7		YN501
0535	20		PA		72-8	27-41-12	D40742P		3		D43404J		7		YR301-YR323, YR325-YR328
3201B	14		MZ	YA	136-11	27-41-12	D00700		3	14	D40616P		3		YC051-YC052
3201B	14		MZ	YA	119-4	27-41-12	D40836P		10	14	D40616P		3		YC053-YC055

WIRE LIST

D280A108

91-21-11

Section W6220

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W6222	286A6222			J4 TO E/E BAY AND STAB TRIM ACTUATOR (continued)										
3201B	14	MZ	YA	119-3	27-41-12	D40836P	10	14		D40616P	3			YC056-YL999, YR301-YR323, YR325-YR328
3201B	14	MZ	YA	99-10	27-41-12	D40836P	10	14		D40616P	3			YN231-YN501
3201R	14	MZ	YA	0-0	27-41-12	D00700	1	14		D40616P	1			YC051-YC052
3201R	14	MZ	YA	0-0	27-41-12	D40836P	4	14		D40616P	1			YC053-YR323, YR325-YR328
3201Y	14	MZ	YA	0-0	27-41-12	D00700	2	14		D40616P	2			YC051-YC052
3201Y	14	MZ	YA	0-0	27-41-12	D40836P	7	14		D40616P	2			YC053-YR323, YR325-YR328
3202B	14	MZ	YB	9-10	27-41-12	D40574P	4			D40602P	4			YC051-YL999, YR301-YR323, YR325-YR328
3202B	14	MZ	YB	9-9	27-41-12	D40574P	4			D40602P	4			YN231-YN501
3202R	14	MZ	YB	0-0	27-41-12	D40574P	5			D40602P	5			YC051-YR323, YR325-YR328
3202Y	14	MZ	YB	0-0	27-41-12	D40574P	6			D40602P	6			YC051-YR323, YR325-YR328
A-A				0-0	27-41-12	S00844	2			S00844	CAP	Y		YC051-YC052
A-B				0-0	27-41-12	S00844	3			S00844	CAP	Y		YC051-YC052
A-C				0-0	27-41-12	S00844	5			S00844	CAP	Y		YC051-YC052
A-E				0-0	27-41-12	S00844	6			SP00154		9		YC051-YC052
A-F				0-0	27-41-12	S00145	6			SP00154		9		YC051-YC052
A-G				0-0	27-41-12	S00145	5			S00145	CAP	Y		YC051-YC052
A-H				0-0	27-41-12	S00844	1			S00844	CAP	Y		YC051-YC052
A-J				0-0	27-41-12	S00844	4			SP00158		9		YC051-YC052
A-K				0-0	27-41-12	S00145	4			SP00160		9		YC051-YC052
YAAA				0-0	27-41-12	GD04801	ST..	E		GD04804	ST..	E	*1	YC051-YC052
YAAB				0-0	27-41-12	GD04801	ST..	E		GD00046	ST..	1		YC051-YC052
YAAC				0-0	27-41-12	GD04801	ST..	E		GD00060	ST..	1		YC051-YC052
YAAD				0-0	27-41-12	GD00060	ST..	1		GD04804	ST..	E	*1	YC051-YC052
YAAE				0-0	27-41-12	GD00060	ST..	1		GD04804	ST..	E		YC051-YC052
YAAF				0-0	27-41-12	GD00060	ST..	1		GD04804	ST..	E		YC051-YC052
W6228	286A6228			DISC AB0500DR TO MAIN WHEEL WELL										
0501	22	PA		24-6	32-42-11	D46048J	2			D40406P	1			YC051-YL999, YR301-YR328
0501	22	PA		24-5	32-42-11	D46048J	2			D40406P	1			YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W6220

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W6228	286A6228				DISC AB0500DR TO MAIN WHEEL WELL (continued)											
0502	22		PA		24-6	32-42-11	D46048J		6		D40406P		2		YC051-YL999, YR301-YR328	
0502	22		PA		24-5	32-42-11	D46048J		6		D40406P		2		YN231-YN501	
0509	22		PA		24-6	31-31-15	D46048J		16		D40406P		9		YC051-YL999, YR301-YR328	
0509	22		PA		24-5	31-31-15	D46048J		16		D40406P		9		YN231-YN501	
0511	22		PA		2-1	32-42-11	D46048J		1		GD00662	DC..	1A		ALL	
0512	22		PA		2-1	32-42-11	D46048J		7		GD00662	DC..	1A		ALL	
0591	22		PA		24-6	32-41-11	D46048J		4		D40406P		3		YC051-YL999, YR301-YR328	
0591	22		PA		24-5	32-41-11	D46048J		4		D40406P		3		YN231-YN501	
0592	22		PA		2-1	32-41-11	D46048J		5		GD00662	DC..	1A		ALL	
2203B	22		X2	KC	24-6	32-42-11	D46048J		14		D40406P		5		YC051-YL999, YR301-YR328	
2203B	22		X2	KC	24-5	32-42-11	D46048J		14		D40406P		5		YN231-YN501	
2203R	22		X2	KC	0-0	32-42-11	D46048J		13		D40406P		4		ALL	
2203Z				KC	0-0	32-42-11	D46048J		15		D40406P		6		ALL	
2204B	22		PB	KD	24-6	32-42-11	D46048J		11		D40406P		8		YC051-YL999, YR301-YR328	
2204B	22		PB	KD	24-5	32-42-11	D46048J		11		D40406P		8		YN231-YN501	
2204R	22		PB	KD	0-0	32-42-11	D46048J		10		D40406P		7		ALL	

WIRE LIST

D280A108

91-21-11
Section W6220
Page 6 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice		
W6230	286A6230				DISC AB0500DR TO E1-3, E4-1 (RB2)											
0001	20		PA		38-3		33-33-11	D43038P	A01			D40058P	9			YC051-YC055
0001	20		PA		38-4		33-33-11	D43038P	A01			D40058P	9			YC056-YL999, YR301-YR323, YR325-YR328 YN231-YN501
0001	20		PA		28-10		33-33-11	D43038P	A01			D40058P	9			YC051-YC055
0301	24		PK		38-3		21-51-22	D43038P	A12			D40058P	5			YC051-YC055
0301	24		PK		38-4		21-51-22	D43038P	A12			D40058P	5			YC056-YL999, YR301-YR323, YR325-YR328
0302	24		PK		38-3		21-51-22	D43038P	A13			D40058P	14			YC051-YC055
0302	24		PK		38-4		21-51-22	D43038P	A13			D40058P	14			YC056-YL999, YR301-YR323, YR325-YR328
0303	24		PK		38-3		21-51-22	D43038P	A14			D40058P	15			YC051-YC055
0303	24		PK		38-4		21-51-22	D43038P	A14			D40058P	15			YC056-YL999, YR301-YR323, YR325-YR328
0304	24		PK		38-3		21-51-22	D43038P	A15			D40058P	20			YC051-YC055
0304	24		PK		38-4		21-51-22	D43038P	A15			D40058P	20			YC056-YL999, YR301-YR323, YR325-YR328
0305	24		PK		41-10		21-51-22	D41806P	A01			D40058P	21			YC051-YL999, YR301-YR323, YR325-YR328
0306	24		PK		41-10		21-51-22	D41806P	A02			D40058P	22			YC051-YL999, YR301-YR323, YR325-YR328
0307	24		PK		41-10		21-51-22	D41806P	A03			D40058P	23			YC051-YL999, YR301-YR323, YR325-YR328
0308	24		PK		41-10		21-51-22	D41806P	A04			D40058P	24			YC051-YL999, YR301-YR323, YR325-YR328
0309	24		PK		41-10		21-51-23	D41806P	A07			D40058P	6			YC051-YL999, YR301-YR323, YR325-YR328
0310	24		PK		41-10		21-51-23	D41806P	A08			D40058P	8			YC051-YL999, YR301-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W6230

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W6230	286A6230				DISC AB0500DR TO E1-3, E4-1 (RB2) (continued)										
0311	24		PK		41-10	21-51-23	D41806P		A09		D40058P		13		YC051-YL999, YR301-YR323, YR325-YR328
0312	24		PK		41-10	21-51-23	D41806P		A10		D40058P		19		YC051-YL999, YR301-YR323, YR325-YR328
0313	24		PK		35-11	21-51-24	D43038P		A02		D00968		10		YC051-YL999, YR301-YR323, YR325-YR328
0314	24		PK		41-10	21-51-24	D41806P		B01		D40058P		16		YC051-YL999, YR301-YR323, YR325-YR328
0315	24		PK		41-10	21-51-24	D41806P		B02		D40058P		17		YC051-YL999, YR301-YR323, YR325-YR328
0316	24		PK		41-10	21-61-13	D41806P		B03		D40058P		18		YC051-YL999, YR301-YR323, YR325-YR328
0317	24		PK		41-10	21-61-13	D41806P		B04		D40058P		25		YC051-YL999, YR301-YR323, YR325-YR328
0318	24		PK		41-10	21-61-13	D41806P		B05		D40058P		26		YC051-YL999, YR301-YR323, YR325-YR328
0319	24		PK		41-10	21-61-14	D41806P		A11		D40058P		27		YC051-YL999, YR301-YR323, YR325-YR328
0320	24		PK		41-10	21-61-14	D41806P		A12		D40058P		28		YC051-YL999, YR301-YR323, YR325-YR328
0321	24		PK		41-10	21-61-14	D41806P		A13		D40058P		29		YC051-YL999, YR301-YR323, YR325-YR328
0323	14		PA		40-0	21-25-11	D40330P		1		D03854		2		YC051-YC055
0323	14		PA		39-11	21-25-11	D40330P		1		D03854		2		YC056-YL999, YR301-YR323, YR325-YR328
0324	14		CQ		40-0	21-25-11	D40330P		2		D03854		3		YC051-YC055

WIRE LIST
D280A108

91-21-11
Section W6230
Page 2
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To				Effectivity	
Wire No.	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W6230	286A6230				DISC AB0500DR TO E1-3, E4-1 (RB2) (continued)											
0324	14		CQ		39-11	21-25-11	D40330P		2		D03854		3		YC056-YL999, YR301-YR323, YR325-YR328	
0325	14		CQ		40-0	21-25-11	D40330P		4		D03854		4		YC051-YC055	
0325	14		CQ		39-11	21-25-11	D40330P		4		D03854		4		YC056-YL999, YR301-YR323, YR325-YR328	
0326	22		CQ		40-0	21-25-11	D40330P		3		D03854		6		YC051-YC055	
0326	22		CQ		39-11	21-25-11	D40330P		3		D03854		6		YC056-YL999, YR301-YR323, YR325-YR328	
0327	20		PA		3-10	21-25-11	D03854		5		GD03254	DC..	1A		YC051-YL999, YR301-YR323, YR325-YR328	
0328	14		PA		3-10	21-25-11	D03854		7		GD03234	ST..	E		YC051-YL999, YR301-YR323, YR325-YR328	
0503	22		PA		38-3	27-83-21	D43038P	B01			D40058P		7		YC051-YC055	
0503	22		PA		38-4	27-83-21	D43038P	B01			D40058P		7		YC056-YL999, YR301-YR323, YR325-YR328	
0503	22		PA		28-10	27-83-21	D43038P	B01			D40058P		7		YN231-YN501	
0521	20		PA		8-8	33-33-11	D40058P		11		SP00420		9		YC051-YL999, YR301-YR323, YR325-YR328	
0521	20		PA		6-3	33-33-11	D40058P		11		SP00420		9		YN231-YN501	
0522	20		PA		8-8	33-33-11	D40058P		12		SP00418		9		YC051-YL999, YR301-YR323, YR325-YR328	
0522	20		PA		6-3	33-33-11	D40058P		12		SP00418		9		YN231-YN501	
2001B	20		PB	GA	35-11	21-51-22	D41806P		A06		D03878		2		YC051-YL999, YR301-YR323, YR325-YR328	
2001R	20		PB	GA	0-0	21-51-22	D41806P		A05		D03878		1		YC051-YL999, YR301-YR323, YR325-YR328	
5501	14		CQ		30-6	21-25-11	D40330P		1		D03020		2		YN231-YN501	
5502	14		CQ		30-6	21-25-11	D40330P		2		D03020		3		YN231-YN501	
5503	14		CQ		30-6	21-25-11	D40330P		4		D03020		4		YN231-YN501	

WIRE LIST

D280A108

91-21-11

Section W6230

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6230	286A6230				DISC AB0500DR TO E1-3, E4-1 (RB2) (continued)										
5504	22		PA		30-6	21-25-11	D40330P		3		D03020		6		YN231-YN501
5507	24		PK		28-10	21-51-24	D43038P		A02		D40058P		16		YN231-YN501
5508	24		PK		1-1	21-51-24	D43038P		B02		SM00001		9		YC051-YC055
5508	24		PK		0-7	21-51-24	D43038P		B02		SM00001		9		YC056-YL999, YR301-YR323, YR325-YR328
5508	24		PK		16-11	21-51-24	D43038P		B02		SM00001		9		YN231-YN501
5509	24		PK		35-11	21-51-24	D43038P		A03		D00968		1		YC051-YL999, YR301-YR323, YR325-YR328
5509	24		PK		25-10	21-51-24	D43038P		A03		D00968		1		YN231-YN501
5510	24		PK		35-11	21-51-24	D43038P		B03		D00968		7		YC051-YL999, YR301-YR323, YR325-YR328
5510	24		PK		25-10	21-51-24	D43038P		B03		D00968		7		YN231-YN501
5511	24		PK		28-10	21-61-22	D40058P		20		D43038P		A04		YN231-YN501
5512	24		PK		28-10	21-61-22	D40058P		21		D43038P		B04		YN231-YN501
5513	20		PA		33-4	21-61-22	D11362		1		D43038P		A05		YN231-YN501
5514	20		PA		33-2	21-61-22	D00518		3		D43038P		B05		YN231-YN501
5515	20		PA		33-2	21-61-22	D00518		1		D43038P		A06		YN231-YN501
5516	22		PA		33-3	21-61-22	D00520		1		D43038P		B06		YN231-YN501
5517	22		PA		33-3	21-61-22	D00520		2		D43038P		A07		YN231-YN501
5518	22		PA		33-3	21-61-22	D00520		3		D43038P		B07		YN231-YN501
5519	24		PK		28-10	21-61-22	D43038P		A08		D40058P		14		YN231-YN501
5520	24		PK		28-10	21-61-22	D43038P		B08		D40058P		15		YN231-YN501
5521	24		PK		38-3	36-21-11	D43038P		A09		D40058P		1		YC051-YC055
5521	24		PK		38-4	36-21-11	D43038P		A09		D40058P		1		YC056-YL999, YR301-YR323, YR325-YR328
5521	24		PK		28-10	36-21-11	D43038P		A09		D40058P		1		YN231-YN501
5522	24		PK		38-3	36-21-11	D43038P		B09		D40058P		2		YC051-YC055
5522	24		PK		38-4	36-21-11	D43038P		B09		D40058P		2		YC056-YL999, YR301-YR323, YR325-YR328
5522	24		PK		28-10	36-21-11	D43038P		B09		D40058P		2		YN231-YN501
5523	24		PK		38-3	36-21-11	D43038P		A10		D40058P		3		YC051-YC055
5523	24		PK		38-4	36-21-11	D43038P		A10		D40058P		3		YC056-YL999, YR301-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W6230

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6230	286A6230			DISC AB0500DR TO E1-3, E4-1 (RB2) (continued)											
5523	24		PK		28-10	36-21-11	D43038P	A10			D40058P	3			YN231-YN501
5525	24		PK		28-10	21-51-26	D43038P	A11			D40058P	5			YN231-YN501
5526	20		PA		38-3	30-71-11	D40058P	31			D43038P	B11			YC051-YC055
5526	20		PA		38-4	30-71-11	D40058P	31			D43038P	B11			YC056-YL999, YR301-YR323, YR325-YR328
5526	20		PA		28-10	30-71-11	D40058P	24			D43038P	B11			YN231-YN501
5527	20		PA		2-7	21-25-11	D03020	5			GD03254	DC..	1A		YN231-YN501
5528	22		PA		10-1	21-51-24	D40058P	18			D00968	10			YN231-YN501
5529	22		PA		13-0	21-51-24	D40058P	17			SM00001		9		YN231-YN501
5530	22		PA		35-5	21-51-24	D00968	5			SM00001		9		YC051-YC055
5530	22		PA		35-11	21-51-24	D00968	5			SM00001		9		YC056-YL999, YR301-YR323, YR325-YR328
5530	22		PA		10-0	21-51-24	D00968	5			SM00001		9		YN231-YN501
5531	22		PA		35-5	21-51-24	D00968	6			SM00001		9		YC051-YC055
5531	22		PA		35-11	21-51-24	D00968	6			SM00001		9		YC056-YL999, YR301-YR323, YR325-YR328
5531	22		PA		10-0	21-51-24	D00968	6			SM00001		9		YN231-YN501
5532	20		PA		3-3	21-51-24	D00968	8			GD00072	DC..	1		YC051-YL999, YR301-YR323, YR325-YR328
5532	20		PA		2-9	21-51-24	D00968	8			GD00072	DC..	1		YN231-YN501
5533	20		PA		3-3	21-51-24	D00968	11			GD00072	AC..	1		YC051-YL999, YR301-YR323, YR325-YR328
5533	20		PA		2-9	21-51-24	D00968	11			GD00072	AC..	1		YN231-YN501
5534	20		PA		6-1	21-61-22	D11362	2			GD03872	DC..	1		YN231-YN501
5535	20		CQ		38-3	30-71-11	D43038P	A16			D40058P	4			YC051-YC055
5535	20		CQ		38-4	30-71-11	D43038P	A16			D40058P	4			YC056-YL999, YR301-YR323, YR325-YR328
5535	20		CQ		28-10	30-71-11	D43038P	A16			D40058P	22			YN231-YN501
5537	24		PK		38-3	21-61-51	D43038P	B10			D40058P	10			YC051-YC055
5537	24		PK		38-4	21-61-51	D43038P	B10			D40058P	10			YC056-YL999, YR301-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W6230

Page 5 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6242	286A6242			P92 TO AB0340B DISCONNECT BRACKET											
0003	20		PA		20-7	33-21-11	D11452	3			D40202P	1			YC051-YN260
0003	18		PA		20-7	33-21-11	D11452	3	18		D40202P	1			YN501-YR328
0013	20		PA		20-7	33-21-11	D11452	13			D40202P	2			YC051-YN260
0013	18		PA		20-7	33-21-11	D11452	13	18		D40202P	2			YN501-YR328
0014	24		PK		20-9	33-21-11	D11452	14			D40050P	2			YC051-YN260
0014	22		PA		20-9	33-21-11	D11452	14			D40050P	2			YN501-YR328
0016	24		PK		20-9	33-21-11	D11452	16			D40050P	1			YC051-YN260
0026	22		PA		22-3	33-26-21	D11452	26			D01128	1			ALL
0034	18		PA		20-7	33-24-11	D11452	18	18		D40202P	4			YN501-YR328
0035	18		PA		35-11	25-29-11	D11452	35			D00156	=P	XR		YC051-YC052
0035	18		PA		35-10	25-29-11	D11452	35			D00156	=P	XR		YC053-YR328
0036	18		PA		20-7	25-29-11	D11452	36			D40202P	24			ALL
0051	18		PA		3-3	25-29-11	GD10086	ST..	1		D00156	=G	XR		ALL
0052	18		PA		3-3	25-29-11	GD10086	AC..	1		D00156	=N	XR		ALL
0053	22		PA		6-1	33-26-21	D11398	1			D01128	2			ALL
0054	22		PA		6-1	33-26-21	D11398	4			D01128	3			ALL
0056	22		PA		6-1	33-26-21	D11398	6			D01128	5			ALL
0057	20		PA		5-1	33-26-21	D11398	2			GD11106	AC..	1		ALL
0058	20		PA		5-1	33-26-21	D11398	3			GD11106	ST..	1		ALL
0059	20		PA		20-9	SPARE	D40050P	8			D11452	CAP	Y		ALL
0060	20		PA		20-9	SPARE	D40050P	9			D11452	CAP	Y		ALL
0509	22		CQ		18-2	29-11-12	D11452	9			D46138P	A06			ALL
0523	22		CQ		18-2	29-11-12	D11452	23			D46138P	A07			ALL
2428B	18		PB	PC	21-0	33-23-21	D40202P	17			GD00690	AC..	E		ALL
2428R	18		PB	PC	0-0	33-23-21	D11452	28			D40202P	7			ALL
2429B	18		PB	PD	21-0	33-23-21	D40202P	18			GD00690	AC..	E		ALL
2429R	18		PB	PD	0-0	33-23-21	D11452	29			D40202P	8			ALL
2430B	18		PB	PE	21-0	33-23-21	D40202P	19			GD00690	AC..	E		ALL
2430R	18		PB	PE	0-0	33-23-21	D11452	30			D40202P	9			ALL
2431B	18		PB	PF	21-1	33-23-21	D40202P	20			GD00692	AC..	E		ALL
2431R	18		PB	PF	0-0	33-23-21	D11452	31			D40202P	10			ALL
2432B	18		PB	PG	21-1	33-23-22	D40202P	21			GD00692	AC..	E		ALL
2432R	18		PB	PG	0-0	33-23-22	D11452	32			D40202P	11			ALL
2433B	18		PB	PH	21-1	33-23-22	D40202P	22			GD00692	AC..	E		ALL
2433R	18		PB	PH	0-0	33-23-22	D11452	33			D40202P	12			ALL
2434B	18		PB	PI	21-2	33-23-22	D40202P	23			GD00694	AC..	E		ALL
2434R	18		PB	PI	0-0	33-23-22	D11452	34			D40202P	13			ALL
2435B	18		PB	PJ	21-2	33-23-22	D40202P	16			GD00694	AC..	E		YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W6240

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W6242	286A6242	P92 TO AB0340B DISCONNECT BRACKET (continued)													
2435R	18	PB	PJ	0-0	33-23-22	D11452	15		D40202P	15			YC051-YL999, YR301-YR328		
2436B	18	PB	PK	21-2	33-23-22	D40202P	6		GD00694	AC..	E		YC051-YL999, YR301-YR328		
2436R	18	PB	PK	0-0	33-23-22	D11452	27		D40202P	5			YC051-YL999, YR301-YR328		
5507	22	CQ		18-2	21-27-31	D11452	7		D46138P	A03			ALL		
5508	22	PA		18-2	21-27-31	D11452	8		D46138P	A02			ALL		
5509	24	PK		19-3	21-27-31	SP02004		S	D46138P	A01			ALL		
W6248	286A6248	AFT CARGO LIGHTS													
0046	20	PA		65-5	52-71-12	D40500P	23		S00961	NO	C		YC051-YC052		
0046	20	PA		65-6	52-71-12	D40500P	23		S00961	NO	C		YC053-YL952		
0046	20	PA		65-11	52-71-12	D40500P	23		SP01246		S		YL953-YL999, YR301-YR328		
0046	20	PA		56-4	52-71-12	D40500P	23		S00961	NO	C		YN231-YN233		
0046	20	PA		56-9	52-71-12	D40500P	23		SP01246		S		YN234-YN236, YN501		
0102	20	PA		6-0	52-71-11	GD03778		AC.. 1	SP01126		9		YC051-YL999, YR301-YR328		
0102	20	PA		7-6	52-71-11	GD03778		AC.. 1	SP01126		9		YN231-YN236, YN501		
0104	20	PA		4-10	52-71-11	GD03810		AC.. 1	SP01146		9		YC051-YL999, YR301-YR328		
0104	20	PA		8-1	52-71-11	GD03810		AC.. 1	SP01146		9		YN231-YN236, YN501		
0120	20	PA		18-8	33-36-12	D12000		1	SM00176		S		YC051-YL999, YR301-YR328		
0146	20	PA		6-6	52-71-12	S00961		C C	GD11794	DC..	1		YC051-YL952, YN231-YN233		
0146	20	PA		6-11	52-71-12	SP01248		S	GD11794	DC..	1		YL953-YL999, YN234-YN236, YN501-YR328		
0168	20	PA		19-11	33-36-12	D11778		1	SM00174		S		YC051-YL999, YR301-YR328		
0168	20	PA		7-5	33-36-12	D11778		1	SM00180		S		YN231-YN236, YN501		
0170	20	PA		11-7	33-36-12	D11770		1	SM00170		S		YC051-YL999, YR301-YR328		
0170	20	PA		12-1	33-36-12	D11770		1	SM00170		S		YN231-YN236, YN501		
0171	20	PA		14-5	33-36-12	SM00170		S	SM00174		S		YC051-YC052		
0171	20	PA		14-6	33-36-12	SM00170		S	SM00174		S		YC053-YL999, YR301-YR328		

WIRE LIST

D280A108

91-21-11

Section W6240

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Description Fam	Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W6248	286A6248			AFT CARGO LIGHTS (continued)										
0171	20	PA		14-3	33-36-12	SM00170		S		SM00174		S		YN231-YN236, YN501
0172	20	PA		14-0	33-36-12	D11772		1		SM00170		S		YC051-YC052
0172	20	PA		14-1	33-36-12	D11772		1		SM00170		S		YC053-YL999, YR301-YR328
0172	20	PA		14-2	33-36-12	D11772		1		SM00170		S		YN231-YN236, YN501
0174	20	PA		7-10	33-36-12	D11774		1		SM00174		S		YC051-YL999, YR301-YR328
0174	20	PA		7-7	33-36-12	D11774		1		SM00174		S		YN231-YN236, YN501
0176	20	PA		19-1	33-36-12	D11776		1		SM00174		S		YC051-YL999, YR301-YR328
0176	20	PA		10-2	33-36-12	D11776		1		SM00174		S		YN231-YN236, YN501
0180	20	PA		30-5	33-36-12	L00195	PWR	C		SM00176		S		YC051-YL999, YR301-YR328
0180	20	PA		15-2	33-36-12	L00195	PWR	C		SM00180		S		YN231-YN236, YN501
0182	20	PA		4-9	33-36-12	D11782		1		SM00184		S		YC051-YL999, YR301-YR328
0182	20	PA		4-8	33-36-12	D11782		1		SM00184		S		YN231-YN236, YN501
0184	20	PA		12-2	33-36-12	D11784		1		SM00184		S		YC051-YN236, YN501-YR328
0185	20	PA		22-1	33-36-12	SM00184		S		SM00176		S		YC051-YL999, YR301-YR328
0185	20	PA		6-0	33-36-12	SM00184		S		SM00180		S		YN231-YN236, YN501
0198	20	PA		11-6	33-36-12	D11998		1		SM00176		S		YC051-YL999, YR301-YR328
0220	20	PA		4-4	33-36-12	D12000		2		GD08040	AC..	1		YC051-YL999, YR301-YR328
0268	20	PA		1-11	33-36-12	D11778		2		GD11774	AC..	1		YC051-YN236, YN501-YR328
0270	20	PA		2-1	33-36-12	D11770		2		GD11728	AC..	1		YC051-YN236, YN501-YR328
0272	20	PA		1-10	33-36-12	D11772		2		GD11730	AC..	1		YC051-YN236, YN501-YR328
0274	20	PA		4-3	33-36-12	D11774		2		GD03760	AC..	1		YC051-YN236, YN501-YR328
0276	20	PA		6-11	33-36-12	D11776		2		GD11774	AC..	1		YC051-YL999, YR301-YR328
0276	20	PA		7-1	33-36-12	D11776		2		GD11774	AC..	1		YN231-YN236, YN501
0280	20	PA		2-7	33-36-12	L00195	GND	C		GD11794	AC..	1		YC051-YL999, YR301-YR328

WIRE LIST
D280A108

91-21-11
Section W6240
Page 3
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To							
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity			
W6248	286A6248			AFT CARGO LIGHTS (continued)													
0280	20		PA		3-5	33-36-12	L00195		GND		C		GD11794	AC..	1		YN231-YN236, YN501
0282	20		PA		1-11	33-36-12	D11782			2			GD11830	AC..	1		YC051-YN236, YN501-YR328
0284	20		PA		1-5	33-36-12	D11784			2			GD11894	AC..	1		YC051-YN236, YN501-YR328
0286	20		PA		7-0	33-36-12	S00068			2	C		GD11794	DC..	1		YC051-YN236, YN501-YR328
0287	20		PA		65-10	33-36-12	D40500P			4			S00068		1	C	YC051-YC052
0287	20		PA		65-11	33-36-12	D40500P			4			S00068		1	C	YC053-YL999, YR301-YR328
0287	20		PA		56-10	33-36-12	D40500P			4			S00068		1	C	YN231-YN236, YN501
0288	20		PA		22-4	33-36-12	D40500P			5			SM00170			S	YC051-YL999, YR301-YR328
0288	20		PA		22-5	33-36-12	D40500P			5			SM00170			S	YN231-YN236, YN501
0298	20		PA		2-0	33-36-12	D11998			2			GD08038	AC..	1		YC051-YL999, YR301-YR328
0384	20		PA		32-1	33-36-12	D40500P			6			SM00176			S	YC051-YC052
0384	20		PA		32-2	33-36-12	D40500P			6			SM00176			S	YC053-YL999, YR301-YR328
0384	20		PA		39-1	33-36-12	D40500P			6			SM00180			S	YN231-YN236, YN501
0499	20		PA		102-4	SPARE	D40500P			1			D00866	CAP	Y		YC051-YC052
0499	20		PA		103-7	SPARE	D40500P			1			D00866	CAP	Y		YC053-YL999, YR301-YR328
0499	20		PA		94-4	SPARE	D40500P			1			D00866	CAP	Y		YN231-YN233
0499	20		PA		94-5	SPARE	D40500P			1			D00866	CAP	Y		YN234-YN236, YN501
0500	20		PA		102-4	SPARE	D40500P			3			D00866	CAP	Y		YC051-YC052
0500	20		PA		103-7	SPARE	D40500P			3			D00866	CAP	Y		YC053-YL999, YR301-YR328
0500	20		PA		94-4	SPARE	D40500P			3			D00866	CAP	Y		YN231-YN233
0500	20		PA		94-5	SPARE	D40500P			3			D00866	CAP	Y		YN234-YN236, YN501
1301R	20		X5	EN	102-4	26-12-11	D40500P			37			D00866	= 1			YC051-YC052
1301R	20		X5	EN	103-7	26-12-11	D40500P			37			D00866	= 1			YC053-YL999, YR301-YR328
1301R	20		X5	EN	94-4	26-12-11	D40500P			37			D00866	= 1			YN231-YN233
1301R	20		X5	EN	94-5	26-12-11	D40500P			37			D00866	= 1			YN234-YN236, YN501
1301Z				EN	0-0	26-12-11	D40500P		DED				D00866	DED			YC051-YN236, YN501-YR328
1302R	20		X5	EP	28-6	26-12-11	D40500P			38			D01070	= 1			YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W6240

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6248	286A6248				AFT CARGO LIGHTS (continued)										
1302R	20	X5	EP		29-2	26-12-11	D40500P	38			D01070	= 1			YN231-YN236, YN501
1302Z			EP		0-0	26-12-11	D40500P	DED			D01070	DED			YC051-YN236, YN501-YR328
2409B	20	PB	OI		80-10	52-71-11	D40500P	11			SP01128		9		YC051-YC052
2409B	20	PB	OI		80-11	52-71-11	D40500P	11			SP01128		9		YC053-YL999, YR301-YR328
2409B	20	PB	OI		73-4	52-71-11	D40500P	11			SP01128		9		YN231-YN236, YN501
2409R	20	PB	OI		0-0	52-71-11	D40500P	26			SP01124		9		YC051-YN236, YN501-YR328
2444B	20	PB	PT		86-3	52-71-11	D40500P	10			SP01148		9		YC051-YC052
2444B	20	PB	PT		86-4	52-71-11	D40500P	10			SP01148		9		YC053-YL999, YR301-YR328
2444B	20	PB	PT		80-2	52-71-11	D40500P	10			SP01148		9		YN231-YN236, YN501
2444R	20	PB	PT		0-0	52-71-11	D40500P	25			SP01144		9		YC051-YN236, YN501-YR328
5501	20	PA			3-9	30-71-11	SP00210		9		GD11996	AC..	1		YC051-YN236, YN501-YR328
5509	20	PA			54-11	30-71-11	D40500P	9			SM00026		9		YC051-YC052
5509	20	PA			55-0	30-71-11	D40500P	9			SM00026		9		YC053-YL999, YR301-YR328
5509	20	PA			45-4	30-71-11	D40500P	9			SM00026		9		YN231-YN236, YN501
5513	20	PA			55-7	30-71-11	D40500P	13			SM00034		9		YC051-YC052
5513	20	PA			55-9	30-71-11	D40500P	13			SM00034		9		YC053-YL999, YR301-YR328
5513	20	PA			46-0	30-71-11	D40500P	13			SM00034		9		YN231-YN236, YN501
5514	20	PA			72-6	30-71-11	D40500P	14			SP00212		9		YC051-YC052
5514	20	PA			72-8	30-71-11	D40500P	14			SP00212		9		YC053-YL999, YR301-YR328
5514	20	PA			63-6	30-71-11	D40500P	14			SP00212		9		YN231-YN236, YN501
5544	20	PA			9-4	30-71-11	SM00026		9		SP00226		9		YC051-YL999, YR301-YR328
5544	20	PA			10-10	30-71-11	SM00026		9		SP00226		9		YN231-YN236, YN501
5545	20	PA			6-9	30-71-11	SP00228		9		GD00028	DC..	1		YC051-YL999, YR301-YR328
5545	20	PA			8-3	30-71-11	SP00228		9		GD00028	DC..	1		YN231-YN236, YN501
5546	20	PA			14-10	30-71-11	SM00026		9		SP00230		9		YC051-YL999, YR301-YR328
5546	20	PA			17-8	30-71-11	SM00026		9		SP00230		9		YN231-YN236, YN501

WIRE LIST

D280A108

91-21-11

Section W6240

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY	Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice
W6248	286A6248	AFT CARGO LIGHTS (continued)			
5547	20 PA	17-4	30-71-11	SP00232	9 GD00028 DC.. 1 YC051-YL999, YR301-YR328
5547	20 PA	20-2	30-71-11	SP00232	9 GD00028 DC.. 1 YN231-YN236, YN501
5548	20 PA	7-8	30-71-11	SM00034	9 D11470 1 YC051-YN236, YN501-YR328
5549	20 PA	5-3	30-71-11	D11470	2 GD00028 AC.. 1 YC051-YN236, YN501-YR328
5550	20 PA	13-10	30-71-11	SM00034	9 D12180 = 1 VS YC051-YN236, YN501-YR328
5551	20 PA	4-5	30-71-11	SP00240	9 GD03740 AC.. 1 YC051-YL999, YR301-YR328
5551	20 PA	6-6	30-71-11	SP00240	9 GD03740 AC.. 1 YN231-YN236, YN501
5552	20 PA	2-7	30-71-11	SM00024	9 SP00238 9 YC051-YL999, YR301-YR328
5552	20 PA	4-1	30-71-11	SM00024	9 SP00238 9 YN231-YN236, YN501
5553	20 PA	3-10	30-71-11	D12186	= 1 VR GD03740 AC.. 1 YC051-YL999, YR301-YR328
5553	20 PA	3-11	30-71-11	D12186	= 1 VR GD03740 AC.. 1 YN231-YN236, YN501
5554	20 PA	2-1	30-71-11	SM00024	9 D12184 = 1 VS YC051-YN236, YN501-YR328
5555	20 PA	2-0	30-71-11	D12190	= 1 VR GD00070 AC.. 1 YC051-YN236, YN501-YR328
5556	20 PA	8-5	30-71-11	D12192	= 1 VS SM00022 9 YC051-YL999, YR301-YR328
5556	20 PA	8-6	30-71-11	D12192	= 1 VS SM00022 9 YN231-YN236, YN501
5559	20 PA	17-1	30-71-11	D12182	= 1 VR GD00028 AC.. 1 YC051-YN236, YN501-YR328
5560	20 PA	2-3	30-71-11	SM00022	9 D12188 = 1 VS YC051-YN236, YN501-YR328
5561	20 PA	8-3	30-71-11	D12194	= 1 VR GD00070 AC.. 1 YC051-YN236, YN501-YR328
5562	20 PA	21-8	30-71-11	SM00034	9 SM00024 9 YC051-YL999, YR301-YR328
5562	20 PA	21-10	30-71-11	SM00034	9 SM00024 9 YN231-YN236, YN501
5563	20 PA	8-4	30-71-11	SM00022	9 SM00024 9 YC051-YL999, YR301-YR328
5563	20 PA	8-5	30-71-11	SM00022	9 SM00024 9 YN231-YN236, YN501
5564	20 PA	2-7	30-71-11	SM00024	9 SP00242 9 YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W6240

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6248	286A6248				AFT CARGO LIGHTS (continued)										
5564	20		PA		4-1	30-71-11	SM00024		9		SP00242		9		YN231-YN236, YN501
5565	20		PA		4-5	30-71-11	SP00244		9		GD03740	AC..	1		YC051-YL999, YR301-YR328
5565	20		PA		6-6	30-71-11	SP00244		9		GD03740	AC..	1		YN231-YN236, YN501
5566	20		PA		12-0	30-71-11	SM00036		9		D12196	=1	VS		YC051-YL999, YR301-YR328
5566	20		PA		12-1	30-71-11	SM00036		9		D12196	=1	VS		YN231-YN236, YN501
5567	20		PA		3-0	30-71-11	D12198	=1	VR		GD11996	AC..	1		YC051-YL999, YR301-YR328
5567	20		PA		3-3	30-71-11	D12198	=1	VR		GD11996	AC..	1		YN231-YN236, YN501
5568	20		PA		5-2	30-71-11	SM00036		9		D12224	=1	VS		YC051-YN236, YN501-YR328
5569	20		PA		7-8	30-71-11	D12226	=1	VR		GD11996	AC..	1		YC051-YL999, YR301-YR328
5569	20		PA		7-7	30-71-11	D12226	=1	VR		GD11996	AC..	1		YN231-YN236, YN501
5570	20		PA		1-3	30-71-11	SM00036		9		D12232	=1	VS		YC051-YN236, YN501-YR328
5571	20		PA		9-3	30-71-11	D12234	=1	VR		GD00028	AC..	1		YC051-YN236, YN501-YR328
5572	20		PA		2-7	30-71-11	SM00030		9		D12204	=1	VS		YC051-YN236, YN501-YR328
5573	20		PA		1-10	30-71-11	D12206	=1	VR		GD00431	AC..	1		YC051-YL999, YR301-YR328
5573	20		PA		1-7	30-71-11	D12206	=1	VR		GD00431	AC..	1		YN231-YN236, YN501
5574	20		PA		1-7	30-71-11	SM00030		9		D12208	=1	VS		YC051-YC052, YN231-YN236, YN501
5574	20		PA		1-6	30-71-11	SM00030		9		D12208	=1	VS		YC053-YL999, YR301-YR328
5575	20		PA		2-1	30-71-11	D12210	=1	VR		GD00431	AC..	1		YC051-YL999, YR301-YR328
5575	20		PA		1-10	30-71-11	D12210	=1	VR		GD00431	AC..	1		YN231-YN236, YN501
5576	20		PA		2-6	30-71-11	SM00030		9		D12212	=1	VS		YC051-YC052
5576	20		PA		2-5	30-71-11	SM00030		9		D12212	=1	VS		YC053-YN236, YN501-YR328
5577	20		PA		1-8	30-71-11	D12214	=1	VR		GD00431	AC..	1		YC051-YL999, YR301-YR328
5577	20		PA		1-5	30-71-11	D12214	=1	VR		GD00431	AC..	1		YN231-YN236, YN501
5578	20		PA		3-6	30-71-11	SM00030		9		D12216	=1	VS		YC051-YC052

WIRE LIST

D280A108

91-21-11
Section W6240
Page 7
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From				To						
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6248	286A6248			AFT CARGO LIGHTS (continued)											
5578	20		PA		3-5	30-71-11	SM00030		9		D12216	= 1	VS		YC053-YL999, YR301-YR328
5578	20		PA		3-11	30-71-11	SM00030		9		D12216	= 1	VS		YN231-YN236, YN501
5579	20		PA		2-3	30-71-11	D12218	= 1	VR		GD00431	AC..	1		YC051-YL999, YR301-YR328
5579	20		PA		2-11	30-71-11	D12218	= 1	VR		GD00431	AC..	1		YN231-YN236, YN501
5580	20		PA		2-6	30-71-11	SM00032		9		D12200	= 1	VS		YC051-YN236, YN501-YR328
5581	20		PA		2-3	30-71-11	D12202	= 1	VR		GD00070	AC..	1		YC051-YN236, YN501-YR328
5582	20		PA		2-9	30-71-11	SM00032		9		D12220	= 1	VS		YC051-YN236, YN501-YR328
5583	20		PA		2-6	30-71-11	D12222	= 1	VR		GD00070	AC..	1		YC051-YN236, YN501-YR328
5584	20		PA		3-7	30-71-11	SM00032		9		D12228	= 1	VS		YC051-YN236, YN501-YR328
5585	20		PA		3-5	30-71-11	D12230	= 1	VR		GD00070	AC..	1		YC051-YN236, YN501-YR328
5587	20		PA		1-4	30-71-11	SM00028		9		SM00036		9		YC051-YN236, YN501-YR328
5588	20		PA		9-6	30-71-11	SM00028		9		SM00030		9		YC051-YC052
5588	20		PA		10-0	30-71-11	SM00028		9		SM00030		9		YC053-YN236, YN501-YR328
5589	20		PA		10-11	30-71-11	SM00028		9		SM00032		9		YC051-YN236, YN501-YR328
5590	20		PA		59-0	30-71-11	D40500P	24			SM00028		9		YC051-YC052
5590	20		PA		59-2	30-71-11	D40500P	24			SM00028		9		YC053-YL999, YR301-YR328
5590	20		PA		49-6	30-71-11	D40500P	24			SM00028		9		YN231-YN236, YN501
A-A					0-0	52-71-12	SP01246		S		S00961	NO	C		YL953-YL999, YN234-YN236, YN501-YR328
A-B					0-0	52-71-12	SP01248		S		S00961		C	C	YL953-YL999, YN234-YN236, YN501-YR328
B-A					0-0	52-71-11	S00200	RED			SP01124		9		YC051-YN236, YN501-YR328
B-B					0-0	52-71-11	S00200	BLU			SP01128		9		YC051-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W6240

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6248	286A6248					AFT CARGO LIGHTS (continued)									
B-C					0-0	52-71-11	S00200		YEL		SP01126		9		YC051-YN236, YN501-YR328
D-A					0-0	52-71-11	S00195		RED		SP01144		9		YC051-YN236, YN501-YR328
D-B					0-0	52-71-11	S00195		BLU		SP01148		9		YC051-YN236, YN501-YR328
D-C					0-0	52-71-11	S00195		YEL		SP01146		9		YC051-YN236, YN501-YR328
E-B					0-0	30-71-11	SP00210			9	M00200		= G		YC051-YN236, YN501-YR328
E-C					0-0	30-71-11	SP00212			9	M00200		GRA		YC051-YN236, YN501-YR328
F-A					0-0	30-71-11	SP00226			9	M01922		= P		YC051-YN236, YN501-YR328
F-B					0-0	30-71-11	SP00228			9	M01922		= G		YC051-YN236, YN501-YR328
G-A					0-0	30-71-11	SP00230			9	M01919		= P		YC051-YN236, YN501-YR328
G-B					0-0	30-71-11	SP00232			9	M01919		= G		YC051-YN236, YN501-YR328
H-A					0-0	30-71-11	SP00238			9	M01907		= P		YC051-YN236, YN501-YR328
H-B					0-0	30-71-11	SP00240			9	M01907		= G		YC051-YN236, YN501-YR328
I-A					0-0	30-71-11	SP00242			9	M01918		= P		YC051-YN236, YN501-YR328
I-B					0-0	30-71-11	SP00244			9	M01918		= G		YC051-YN236, YN501-YR328

WIRE LIST
D280A108

91-21-11
Section W6240
Page 9 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6288	286A6288			AB0340B, E3-3, E4-1 TO TEMPERATURE SENSORS											
0001	20		PA		50-9	21-61-13	D41816P	A01			D11834	1			YC051-YC055
0001	20		PA		52-0	21-61-13	D41816P	A01			D11834	1			YC056-YL999
0001	20		PA		51-11	21-61-13	D41816P	A01			D11834	1			YR301-YR328
0002	20		PA		7-9	21-61-13	D11834	2			GD08010	DC..	1		YC051-YL999, YR301-YR328
0003	24		PK		31-10	21-61-13	D41818P	A05			D41820P	1			YC051-YC055
0003	24		PK		31-11	21-61-13	D41818P	A05			D41820P	1			YC056-YL999
0003	24		PK		33-1	21-61-13	D41818P	A05			D41027P	1			YR301-YR328
0004	20		PA		3-8	21-61-13	D41820P	6			GD03858	AC..	1A		YC051-YL999
0004	20		PA		4-10	21-61-13	D41027P	6			GD03858	AC..	1A		YR301-YR328
0005	20		PA		3-8	21-61-13	D41820P	7			GD03858	ST..	1A		YC051-YL999
0005	20		PA		4-10	21-61-13	D41027P	7			GD03858	ST..	1A		YR301-YR328
0006	20		PA		54-6	21-61-14	D41816P	A02			D11836	1			YC051-YC055
0006	20		PA		55-4	21-61-14	D41816P	A02			D11836	1			YC056-YL999, YR301-YR328
0007	20		PA		6-10	21-61-14	D11836	2			GD08018	DC..	1		YC051-YL999, YR301-YR328
0008	24		PK		88-5	21-61-14	D41818P	B03			D41834P	1			YC051-YC055
0008	24		PK		88-6	21-61-14	D41818P	B03			D41834P	1			YC056-YL999
0008	24		PK		87-4	21-61-14	D41818P	B03			D41028P	1			YR301-YR328
0009	20		PA		4-0	21-61-14	D41834P	6			GD08026	AC..	1		YC051-YL999
0009	20		PA		9-4	21-61-14	D41028P	6			GD08026	AC..	1		YR301-YR328
0010	20		PA		4-0	21-61-14	D41834P	7			GD08026	ST..	1		YC051-YL999
0010	20		PA		9-4	21-61-14	D41028P	7			GD08026	ST..	1		YR301-YR328
0011	20		PA		34-0	21-61-51	D41838J	1			D11832	B			YC051-YL999
0011	20		PA		33-11	21-61-51	D41838J	1			D11832	B			YR301-YR328
0012	20		PA		7-9	21-61-51	D11832	A			GD08010	DC..	1		YC051-YL999, YR301-YR328
0013	24		PK		12-1	21-61-51	D41838J	3			D41820P	9			YC051-YL999
0013	24		PK		13-3	21-61-51	D41838J	3			D41027P	9			YR301-YR328
0014	20		PA		3-8	21-61-51	D41820P	8			GD03858	DC..	1A		YC051-YL999
0014	20		PA		4-10	21-61-51	D41027P	8			GD03858	DC..	1A		YR301-YR328
0015	24		PK		68-8	21-61-51	D41838J	4			D41834P	9			YC051-YC058
0015	20		PA		68-8	21-61-51	D41838J	4			D41834P	9			YC059-YL999
0015	20		PA		67-6	21-61-51	D41838J	4			D41028P	9			YR301-YR328
0016	20		PA		4-0	21-61-51	D41834P	8			GD08026	DC..	1		YC051-YL999
0016	20		PA		9-4	21-61-51	D41028P	8			GD08026	DC..	1		YR301-YR328
0017	20		PA		37-3	21-61-51	D41838J	2			D11838	B			YC051-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W6280

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W6288	286A6288				AB0340B, E3-3, E4-1 TO TEMPERATURE SENSORS (continued)											
0018	20		PA		6-9	21-61-51		D11838		A		GD08018	DC..	1		YC051-YL999, YR301-YR328
2001B	20		PB	GA	54-2	21-61-13		D41818P		A03		D11830		1		YC051-YC055, YR301-YR328
2001B	20		PB	GA	54-3	21-61-13		D41818P		A03		D11830		1		YC056-YL999
2001R	20		PB	GA	0-0	21-61-13		D41818P		A04		D11830		2		YC051-YL999, YR301-YR328
2002B	24		PL	GB	31-10	21-61-13		D41818P		A06		D41820P		2		YC051-YC055
2002B	24		PL	GB	31-11	21-61-13		D41818P		A06		D41820P		2		YC056-YL999
2002B	24		PL	GB	33-1	21-61-13		D41818P		A06		D41027P		2		YR301-YR328
2002R	24		PL	GB	0-0	21-61-13		D41818P		A07		D41820P		3		YC051-YL999
2002R	24		PL	GB	0-0	21-61-13		D41818P		A07		D41027P		3		YR301-YR328
2003B	24		PL	GC	31-10	21-61-13		D41818P		A09		D41820P		5		YC051-YC055
2003B	24		PL	GC	31-11	21-61-13		D41818P		A09		D41820P		5		YC056-YL999
2003B	24		PL	GC	33-1	21-61-13		D41818P		A09		D41027P		5		YR301-YR328
2003R	24		PL	GC	0-0	21-61-13		D41818P		A08		D41820P		4		YC051-YL999
2003R	24		PL	GC	0-0	21-61-13		D41818P		A08		D41027P		4		YR301-YR328
2004B	20		PB	GD	57-6	21-61-14		D41818P		B01		D11840		1		YC051-YC055
2004B	20		PB	GD	57-7	21-61-14		D41818P		B01		D11840		1		YC056-YL999, YR301-YR328
2004R	20		PB	GD	0-0	21-61-14		D41818P		B02		D11840		2		YC051-YL999, YR301-YR328
2005B	24		PL	GE	88-5	21-61-14		D41818P		B04		D41834P		2		YC051-YC055
2005B	24		PL	GE	88-6	21-61-14		D41818P		B04		D41834P		2		YC056-YL999
2005B	24		PL	GE	87-4	21-61-14		D41818P		B04		D41028P		2		YR301-YR328
2005R	24		PL	GE	0-0	21-61-14		D41818P		B05		D41834P		3		YC051-YL999
2005R	24		PL	GE	0-0	21-61-14		D41818P		B05		D41028P		3		YR301-YR328
2006B	24		PL	GF	88-5	21-61-14		D41818P		B07		D41834P		5		YC051-YC055
2006B	24		PL	GF	88-6	21-61-14		D41818P		B07		D41834P		5		YC056-YL999
2006B	24		PL	GF	87-4	21-61-14		D41818P		B07		D41028P		5		YR301-YR328
2006R	24		PL	GF	0-0	21-61-14		D41818P		B06		D41834P		4		YC051-YL999
2006R	24		PL	GF	0-0	21-61-14		D41818P		B06		D41028P		4		YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W6280

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I	W6410	286A6410			P92 (AFT DISC) TO E/E BAY											
I	0009	20		PA		2-7	33-36-12	D11454		9		D40382P	A15			ALL
I	0021	20		PA		2-7	33-36-11	D11454		21		D40382P	B14			ALL
I	0023	20		PA		2-7	33-36-12	D11454		23		D40382P	A14			ALL
I	0039	20		PA		2-7	33-36-11	D11454		39		D40382P	B15			ALL
I	0042	20		PA		2-7	33-33-11	D11454		42		D40382P	A16			ALL
I	0501	22		PA		2-7	24-23-51	D40382P		A01		D11454	6			ALL
I	0503	22		PA		2-7	24-28-41	D40382P		A02		D11454	4			ALL
I	0504	22		PA		2-7	24-28-41	D40382P		B02		D11454	5			ALL
I	0505	22		CQ		2-7	24-22-31	D11454		12		D40382P	A18			ALL
I	0506	20		PA		3-6	24-51-21	D11454		7		GD00922	DC..	E		ALL
I	0510	20		CQ		2-9	29-11-12	D11454		3		SP00012		S		ALL
I	0514	22		PA		2-7	24-23-21	D40382P		A03		D11454	29			ALL
I	0515	22		PA		2-7	24-23-21	D40382P		B03		D11454	15			ALL
I	0516	22		PA		2-7	24-22-21	D40382P		A04		D11454	50			ALL
I	0517	22		PA		2-7	24-22-21	D40382P		B04		D11454	32			ALL
I	0518	22		PA		2-7	24-22-21	D40382P		A05		D11454	33			ALL
I	0519	22		PA		2-7	24-22-21	D40382P		B05		D11454	14			ALL
I	0520	22		CQ		2-7	24-22-11	D40382P		B18		D11454	13			ALL
I	2201B	20		PB	KA	2-7	24-41-11	D40382P		B06		D11454	1			ALL
I	2201R	20		PB	KA	0-0	24-41-11	D40382P		A06		D11454	58			ALL
I	3201B	20		PC	YA	2-7	24-22-21	D40382P		B07		D11454	56			ALL
I	3201R	20		PC	YA	0-0	24-22-21	D40382P		A07		D11454	55			ALL
I	3201Y	20		PC	YA	0-0	24-22-21	D40382P		A08		D11454	53			ALL
I	3202B	20		PC	YB	2-7	24-23-21	D11454		48		D40382P	A09			ALL
I	3202R	20		PC	YB	0-0	24-23-21	D11454		49		D40382P	B08			ALL
I	3202Y	20		PC	YB	0-0	24-23-21	D11454		51		D40382P	B09			ALL
I	4101B	22		PD	N6	2-7	24-24-21	D40382P		B10		D11454	47			ALL
I	4101G	22		PD	N6	0-0	24-24-21	D40382P		A11		D11454	27			ALL
I	4101R	22		PD	N6	0-0	24-24-21	D40382P		A10		D11454	46			ALL
I	4101Y	22		PD	N6	0-0	24-24-21	D40382P		B11		D11454	26			ALL
I	4102B	22		PD	P6	2-7	24-41-11	D40382P		B12		D11454	44			ALL
I	4102G	22		PD	P6	0-0	24-41-11	D40382P		A13		D11454	24			ALL
I	4102R	22		PD	P6	0-0	24-41-11	D40382P		A12		D11454	45			ALL
I	4102Y	22		PD	P6	0-0	24-41-11	D40382P		B13		D11454	25			ALL
I	5501	22		PA		2-7	21-27-31	D11454		8		D40382P	B20			ALL
I	W6412	286A6412			AP0600B TO E3 AND E4 (RB2)											
	0002	20		PA		3-7	33-33-11	D40388P		A18		D40390P	B17			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W6410

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6412	286A6412				AP0600B TO E3 AND E4 (RB2) (continued)										
0002	20		PA		3-9	33-33-11	D40388P	A18			D40390P	B17			YC056-YN236, YN501-YR323, YR325-YR328
0005	20		PA		7-9	52-71-11	SP01160		9		GD03880	AC..	1		YC051-YN236, YN501-YR323, YR325-YR328
0007	24		PK		9-0	31-62-24	D40394P	A17			D40388P	A19			YC051-YC055
0007	24		PK		9-2	31-62-24	D40394P	A17			D40388P	A19			YC056-YN236, YN501-YR323, YR325-YR328
0008	20		PA		19-2	SPARE	D40386P		27		D41010P		18		YC067-YN236, YN501-YR323, YR325-YR328
0009	20		PA		19-2	SPARE	D40386P		31		D41010P		19		YC067-YN236, YN501-YR323, YR325-YR328
0010	20		PA		19-2	SPARE	D40386P		32		D41010P		20		YC067-YN236, YN501-YR323, YR325-YR328
0029	20		PA		19-9	SPARE	D41832P		7		D41830P		A06		YC067-YL967, YR301-YR323, YR325-YR328
0029	20		PA		19-9	23-32-11	D41832P		7		D41830P		A06		YL968-YL999
0030	24		PK		4-6	21-31-23	D41830P	A10			D40712P		7		YC067-YD157
0031	24		PK		4-6	21-31-23	D41830P	A11			D40712P		8		YC067-YD157
0032	20		PA		4-6	21-31-23	D41830P	A12			D40712P		9		YC067-YD157
0033	20		PA		10-1	27-62-41	D11841		4		D40386P		24		YN231-YN236, YN501
0034	20		PA		10-1	27-62-41	D11841		5		D40386P		23		YN231-YN236, YN501
0035	20		PA		10-1	27-62-41	D11841		3		D40386P		29		YN231-YN236, YN501
0036	20		PA		10-1	27-62-41	D11841		7		D40386P		9		YN231-YN236, YN501
0037	20		PA		4-3	27-62-41	D11841		1		GD00053	DC..	E		YN231-YN236, YN501
0038	20		PA		4-3	27-62-41	D11841		2		GD00053	DC..	E		YN231-YN236, YN501
0039	20		PA		4-3	27-62-41	D11841		6		GD00053	DC..	E		YN231-YN236, YN501
0040	20		PA		10-7	31-31-15	D40392P		B15		D40388P		B01		YC051-YN236, YN501-YR323, YR325-YR328
0041	20		PA		10-7	31-31-15	D40392P		B16		D40388P		B02		YC051-YN236, YN501-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W6410

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6412	286A6412			AP0600B TO E3 AND E4 (RB2) (continued)											
0042	22		PA		10-2	27-62-11	D43080P	B06			D40388P	B13			YL953-YL999, YR301-YR323, YR325-YR328
0043	22		PA		10-2	27-62-11	D43080P	B07			D40388P	B10			YL953-YL999, YR301-YR323, YR325-YR328
0200	24		B6		8-9	21-51-21	D40390P	B14			D40392P	B14			YD158-YN236, YN501-YR323, YR325-YR328
0201	22		CQ		18-3	23-51-51	D40386P	11			D40390P	A03			YC051-YC055
0201	22		CQ		18-0	23-51-51	D40386P	11			D40390P	A03			YC056-YN236, YN501-YR323, YR325-YR328
0202	22		CQ		18-3	23-51-51	D40386P	12			D40390P	A10			YC051-YC055
0202	22		CQ		18-0	23-51-51	D40386P	12			D40390P	A10			YC056-YN236, YN501-YR323, YR325-YR328
0203	20		PA		4-6	21-31-23	D40712P	2			D41830P	B11			YD158-YN236, YN501-YR323, YR325-YR328
0204	24		PK		4-6	21-31-23	D40712P	10			D41830P	B12			YD158-YN236, YN501-YR323, YR325-YR328
0301	24		PK		20-4	21-51-22	D41832P	1			D41830P	A01			YC051-YC055
0301	24		PK		19-9	21-51-22	D41832P	1			D41830P	A01			YC056-YL999, YR301-YR323, YR325-YR328
0302	24		PK		23-7	21-51-22	D41832P	2			D41822P	A01			YC051-YC055
0302	24		PK		23-5	21-51-22	D41832P	2			D41822P	A01			YC056-YL999, YR301-YR323, YR325-YR328
0303	24		PK		23-7	21-51-22	D41832P	3			D41822P	A02			YC051-YC055
0303	24		PK		23-5	21-51-22	D41832P	3			D41822P	A02			YC056-YL999, YR301-YR323, YR325-YR328
0310	24		PK		19-9	21-51-22	D41832P	19			D41830P	B04			YC065-YL999, YR301-YR323, YR325-YR328
0501	22		PA		20-2	24-23-51	D40386P	14			D40388P	A02			YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W6410

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice			
W6412	286A6412				AP0600B TO E3 AND E4 (RB2) (continued)												
0501	22		PA		20-0	24-23-51	D40386P		14		D40388P	A02			YC056-YN236, YN501-YR323, YR325-YR328		
0502	22		PA		20-2	24-23-51	D40386P		16		D40388P	A03			YC051-YC055		
0502	22		PA		20-0	24-23-51	D40386P		16		D40388P	A03			YC056-YN236, YN501-YR323, YR325-YR328		
0503	22		PA		10-0	27-62-11	D43080P		A08		D40388P	A04			YC051-YC055		
0503	22		PA		10-2	27-62-11	D43080P		A08		D40388P	A04			YC056-YN236, YN501-YR323, YR325-YR328		
0504	22		PA		10-0	27-62-11	D43080P		A09		D40388P	A05			YC051-YC055		
0504	22		PA		10-2	27-62-11	D43080P		A09		D40388P	A05			YC056-YN236, YN501-YR323, YR325-YR328		
0505	22		PA		22-5	27-83-21	D40386P		3		D40392P	A02			YC051-YC055		
0505	22		PA		22-4	27-83-21	D40386P		3		D40392P	A02			YC056-YN236, YN501-YR323, YR325-YR328		
0506	22		PA		8-9	27-83-21	D40392P		A03		D40390P	A07			YC051-YN236, YN501-YR323, YR325-YR328		
0507	22		PA		8-9	27-83-21	D40390P		A02		D40392P	A04			YC051-YN236, YN501-YR323, YR325-YR328		
0508	20		PA		8-7	SPARE	D40394P		A09		D41010P	2			YC051-YC055		
0508	20		PA		8-4	SPARE	D40394P		A09		D41010P	2			YC056-YN236, YN501-YR323, YR325-YR328		
0509	20		PA		23-7	29-31-11	D40394P		B09		SP00476		S		YC051-YC055		
0509	20		PA		24-0	29-31-11	D40394P		B09		SP00476		S		YC056-YN236, YN501-YR323, YR325-YR328		
0510	20		PA		23-7	29-31-11	D40394P		A10		SP00474		S		YC051-YC055		
0510	20		PA		24-0	29-31-11	D40394P		A10		SP00474		S		YC056-YN236, YN501-YR323, YR325-YR328		
0512	24		PK		10-8	27-21-11	D40392P		A20		D40388P	B19			YC051-YC055		

WIRE LIST

D280A108

91-21-11

Section W6410

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6412		286A6412				AP0600B TO E3 AND E4 (RB2) (continued)										
0512		24		PK		10-9	27-21-11	D40392P	A20			D40388P	B19			YC056-YN236, YN501-YR323, YR325-YR328
0513		24		PK		10-8	27-21-11	D40392P	B20			D40388P	B20			YC051-YC055
0513		24		PK		10-9	27-21-11	D40392P	B20			D40388P	B20			YC056-YN236, YN501-YR323, YR325-YR328
0514		20		PA		23-7	29-31-11	D40394P	B10			SP00472		S		YC051-YC055
0514		20		PA		24-0	29-31-11	D40394P	B10			SP00472		S		YC056-YN236, YN501-YR323, YR325-YR328
0515		22		PA		23-0	29-23-11	D40388P	B05			SP00478		S		YC051-YC055
0515		22		PA		23-4	29-23-11	D40388P	B05			SP00478		S		YC056-YN236, YN501-YR323, YR325-YR328
0516		24		PK		8-7	29-32-11	D40394P	B14			D41010P	14			YC051-YC055
0516		24		PK		8-4	29-32-11	D40394P	B14			D41010P	14			YC056-YN236, YN501-YR323, YR325-YR328
0517		24		PK		8-7	29-32-11	D40394P	B15			D41010P	15			YC051-YC055
0517		24		PK		8-4	29-32-11	D40394P	B15			D41010P	15			YC056-YN236, YN501-YR323, YR325-YR328
0518		24		PK		8-8	29-33-11	D40390P	A01			D40392P	A08			YC051-YL999, YR301-YR323, YR325-YR328
0518		24		PK		8-9	29-33-11	D40390P	A01			D40392P	A08			YN231-YN236, YN501
0519		24		PK		10-0	27-11-11	D40388P	B16			D43080P	A05			YC051-YC055
0519		24		PK		10-2	27-11-11	D40388P	B16			D43080P	A05			YC056-YN236, YN501-YR323, YR325-YR328
0520		24		PK		10-0	27-11-11	D40388P	B17			D43080P	A04			YC051-YC055
0520		24		PK		10-2	27-11-11	D40388P	B17			D43080P	A04			YC056-YN236, YN501-YR323, YR325-YR328
1001		22		X1	AA	2-11	31-62-24	D40394P	A16			D40392P	A15			YC051-YC055
1001		22		X1	AA	3-0	31-62-24	D40394P	A16			D40392P	A15			YC056-YN236, YN501-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W6410

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6412	286A6412				AP0600B TO E3 AND E4 (RB2) (continued)											
1001Z				AA	0-0	31-62-24		D40394P	PERG	1F		D40392P	PERG	1F		YC051-YN236, YN501-YR323, YR325-YR328
1002	20	X1		AB	10-0	27-62-11		D43080P	A06			D40388P	A10			YC051-YL999, YR301-YR323, YR325-YR328
1002	20	X1		AB	9-11	27-62-11		D43080P	A06			D40388P	A10			YN231-YN236, YN501
1002Z				AB	0-0	27-62-11		D43080P	A07			D40388P	A17			YC051-YN236, YN501-YR323, YR325-YR328
1301	20	X1		EN	3-7	73-22-11		D40388P	B11			D40390P	A04			YC051-YC055
1301	20	X1		EN	3-9	73-22-11		D40388P	B11			D40390P	A04			YC056-YN236, YN501-YR323, YR325-YR328
1301Z				EN	0-0	73-22-11		D40388P	PERG	1F		D40390P	PERG	1F		YC051-YN236, YN501-YR323, YR325-YR328
1302R	20	X5		EP	8-7	26-11-21		D41010P	16			D40394P	A18			YC051-YC055
1302R	20	X5		EP	8-4	26-11-21		D41010P	16			D40394P	A18			YC056-YN236, YN501-YR323, YR325-YR328
1302Z				EP	0-0	26-11-21		D41010P	DED			D40394P	DED			YC051-YN236, YN501-YR323, YR325-YR328
1303R	20	X5		EQ	8-7	26-11-21		D41010P	17			D40394P	B18			YC051-YC055
1303R	20	X5		EQ	8-4	26-11-21		D41010P	17			D40394P	B18			YC056-YN236, YN501-YR323, YR325-YR328
1303Z				EQ	0-0	26-11-21		D41010P	DED			D40394P	DED			YC051-YN236, YN501-YR323, YR325-YR328
2001B	24	Y2		GA	8-9	27-32-22		D40392P	B18			D40390P	A06			YC051-YD157
2001B	24	Y2		GA	8-9	SPARE		D40392P	B18			D40390P	A06			YD158-YN236, YN501-YR323, YR325-YR328
2001R	24	Y2		GA	0-0	27-32-22		D40392P	B17			D40390P	A05			YC051-YD157
2001R	24	Y2		GA	0-0	SPARE		D40392P	B17			D40390P	A05			YD158-YN236, YN501-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W6410

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Fam	Description FT-IN Diagram		From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W6412	286A6412				AP0600B TO E3 AND E4 (RB2) (continued)										
2001Z				GA	0-0	27-32-22	D40392P	PERG	1F		D40390P	PERG	1F		YC051-YD157
2001Z				GA	0-0	SPARE	D40392P	PERG	1F		D40390P	PERG	1F		YD158-YN236, YN501-YR323, YR325-YR328
2201B	22	PB	KA		20-2	24-23-51	D40386P		18		D40388P	A06			YC051-YC055
2201B	22	PB	KA		20-0	24-23-51	D40386P		18		D40388P	A06			YC056-YN236, YN501-YR323, YR325-YR328
2201R	22	PB	KA		0-0	24-23-51	D40386P		20		D40388P	A07			YC051-YN236, YN501-YR323, YR325-YR328
2202B	22	PB	KB		4-3	24-41-11	D41010P		8		D40388P	A11			YC051-YC055
2202B	22	PB	KB		4-1	24-41-11	D41010P		8		D40388P	A11			YC056-YN236, YN501-YR323, YR325-YR328
2202R	22	PB	KB		0-0	24-41-11	D41010P		7		D40388P	A12			YC051-YN236, YN501-YR323, YR325-YR328
2203B	22	PB	KC		4-3	24-41-11	D41010P		9		D40388P	A13			YC051-YC055
2203B	22	PB	KC		4-1	24-41-11	D41010P		9		D40388P	A13			YC056-YN236, YN501-YR323, YR325-YR328
2203R	22	PB	KC		0-0	24-41-11	D41010P		10		D40388P	A14			YC051-YN236, YN501-YR323, YR325-YR328
2401B	20	PB	OA		19-5	52-71-11	D40388P	B03			SP01162		9		YC051-YC055
2401B	20	PB	OA		19-9	52-71-11	D40388P	B03			SP01162		9		YC056-YN236, YN501-YR323, YR325-YR328
2401R	20	PB	OA		0-0	52-71-11	D40388P	B04			SP01158		9		YC051-YN236, YN501-YR323, YR325-YR328
2601B	20	X2	SA		7-1	73-24-21	D40394P	A05			D40390P	A08			YC051-YN236, YN501-YR323, YR325-YR328
2601R	20	X2	SA		0-0	73-24-21	D40394P	A06			D40390P	A09			YC051-YN236, YN501-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W6410

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W6412	286A6412				AP0600B TO E3 AND E4 (RB2) (continued)											
2601Z				SA	0-0	73-24-21		D40394P	PERG	1F		D40390P	PERG	1F	YC051-YN236, YN501-YR323, YR325-YR328	
2602B	24	Y2	SB		7-1	77-12-21		D40394P	A07			D40390P	A12		YC051-YN236, YN501-YR323, YR325-YR328	
2602R	24	Y2	SB		0-0	77-12-21		D40394P	A08			D40390P	A11		YC051-YN236, YN501-YR323, YR325-YR328	
2602Z				SB	0-0	77-12-21		D40394P	PERG	1F		D40390P	PERG	1F	YC051-YN236, YN501-YR323, YR325-YR328	
2604B	22	PB	SD		8-9	78-36-21		D40392P	A09			D40390P	A14		YC051-YN236, YN501-YR323, YR325-YR328	
2604R	22	PB	SD		0-0	78-36-21		D40392P	A10			D40390P	A13		YC051-YN236, YN501-YR323, YR325-YR328	
2605B	22	PB	SE		8-9	78-36-21		D40392P	A11			D40390P	A16		YC051-YN236, YN501-YR323, YR325-YR328	
2605R	22	PB	SE		0-0	78-36-21		D40392P	A12			D40390P	A15		YC051-YN236, YN501-YR323, YR325-YR328	
2606B	24	Y2	SF		7-1	73-24-12		D40394P	B19			D40390P	B16		YC051-YN236, YN501-YR323, YR325-YR328	
2606R	24	Y2	SF		0-0	73-24-12		D40394P	A19			D40390P	B15		YC051-YN236, YN501-YR323, YR325-YR328	
2606Z				SF	0-0	73-24-12		D40394P	PERG	1F		D40390P	PERG	1F	YC051-YN236, YN501-YR323, YR325-YR328	
2607B	22	X2	SG		9-0	28-41-11		D40388P	A15			D40394P	A11		YC051-YC055	
2607B	22	X2	SG		9-2	28-41-11		D40388P	A15			D40394P	A11		YC056-YN236, YN501-YR323, YR325-YR328	

WIRE LIST
D280A108

91-21-11
Section W6410
Page 8
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6412	286A6412			AP0600B TO E3 AND E4 (RB2) (continued)											
2607R	22	X2	SG		0-0	28-41-11	D40388P	B15			D40394P	A12			YC051-YN236, YN501-YR323, YR325-YR328
2607Z			SG		0-0	28-41-11	D40388P	PERG	1F		D40394P	PERG	1F		YC051-YN236, YN501-YR323, YR325-YR328
2608B	24	Y2	SH		2-11	SPARE	D40394P	A13			D40392P	A05			YC051-YC055
2608B	24	Y2	SH		3-0	SPARE	D40394P	A13			D40392P	A05			YC056-YN236, YN501-YR323, YR325-YR328
2608R	24	Y2	SH		0-0	SPARE	D40394P	A14			D40392P	A06			YC051-YN236, YN501-YR323, YR325-YR328
2608Z			SH		0-0	SPARE	D40394P	PERG	1F		D40392P	PERG	1F		YC051-YN236, YN501-YR323, YR325-YR328
2610B	22	VX	SJ		8-1	77-31-21	D40390P	B11			D43080P	A01			YC051-YC055
2610B	22	VX	SJ		8-2	77-31-21	D40390P	B11			D43080P	A01			YC056-YN236, YN501-YR323, YR325-YR328
2610W	22	VX	SJ		0-0	77-31-21	D40390P	B12			D43080P	A02			YC051-YN236, YN501-YR323, YR325-YR328
2610Z			SJ		0-0	77-31-21	D40390P	B13			D43080P	A03			YC051-YN236, YN501-YR323, YR325-YR328
2611B	22	VX	SK		2-4	77-31-21	D43080P	B08			D40394P	B11			YC051-YN236, YN501-YR323, YR325-YR328
2611W	22	VX	SK		0-0	77-31-21	D43080P	B09			D40394P	B12			YC051-YN236, YN501-YR323, YR325-YR328
2611Z			SK		0-0	77-31-21	D43080P	B10			D40394P	B13			YC051-YN236, YN501-YR323, YR325-YR328
2612B	24	Y2	SL		3-7	73-21-11	D40388P	B09			D40390P	B19			YC051-YC055
2612B	24	Y2	SL		3-9	73-21-11	D40388P	B09			D40390P	B19			YC056-YN236, YN501-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W6410

Page 9

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Description Fam	Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W6412	286A6412			AP0600B TO E3 AND E4 (RB2) (continued)										
2612R	24	Y2	SL		0-0 73-21-11	D40388P	B08			D40390P	B18			YC051-YN236, YN501-YR323, YR325-YR328
2612Z			SL		0-0 73-21-11	D40388P	PERG	1F		D40390P	PERG	1F		YC051-YN236, YN501-YR323, YR325-YR328
2801B	24	Y2	A8		8-9 34-21-24	D40390P	B02			D40392P	B02			YC051-YD157
2801R	24	Y2	A8		0-0 34-21-24	D40390P	B01			D40392P	B01			YC051-YD157
2801Z			A8		0-0 34-21-24	D40390P	PERG	1F		D40392P	PERG	1F		YC051-YD157
5501	14	PA			19-4 21-25-11	D40386P		1		D40326P		1		YC051-YC055
5501	14	PA			19-0 21-25-11	D40386P		1		D40326P		1		YC056-YN236, YN501-YR323, YR325-YR328
5502	14	PA			19-4 21-25-11	D40386P		2		D40326P		2		YC051-YC055
5502	14	PA			19-0 21-25-11	D40386P		2		D40326P		2		YC056-YN236, YN501-YR323, YR325-YR328
5503	14	PA			19-4 21-25-11	D40386P		4		D40326P		3		YC051-YC055
5503	14	PA			19-0 21-25-11	D40386P		4		D40326P		3		YC056-YN236, YN501-YR323, YR325-YR328
5504	24	PK			8-9 SPARE	D40390P	B03			D40392P	B03			YC051-YN236, YN501-YR323, YR325-YR328
5508	22	PA			18-3 SPARE	D40386P		9		D40390P	A19			YC051-YC055
5508	22	PA			18-0 SPARE	D40386P		9		D40390P	A19			YC056-YL999, YR301-YR323, YR325-YR328
5512	22	PA			18-3 21-51-24	D40386P		7		D40390P	B07			YC051-YC055
5512	22	PA			18-0 21-51-24	D40386P		7		D40390P	B07			YC056-YN236, YN501-YR323, YR325-YR328
5513	24	PK			18-3 21-51-24	D40386P		19		D40390P	B20			YC051-YC055
5513	24	PK			18-0 21-51-24	D40386P		19		D40390P	B20			YC056-YN236, YN501-YR323, YR325-YR328
5514	24	PK			8-9 21-51-24	D40390P	B04			D40392P	B04			YC051-YN236, YN501-YR323, YR325-YR328

WIRE LIST
D280A108

91-21-11
Section W6410
Page 10
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W6412	286A6412				AP0600B TO E3 AND E4 (RB2) (continued)												
5515	24		PK		8-9		21-51-24	D40390P		B05		D40392P		B05		YC051-YN236, YN501-YR323, YR325-YR328	
5516	24		PK		18-0		21-51-26	D40386P		21		D40390P		A20		YN231-YN236, YN501	
5519	24		PK		18-3		21-31-23	D40386P		13		D40390P		B08		YC051-YC055	
5519	24		PK		18-0		21-31-23	D40386P		13		D40390P		B08		YC056-YD157	
5520	20		PA		18-3		21-31-23	D40386P		22		D40390P		B09		YC051-YC055	
5520	20		PA		18-0		21-31-23	D40386P		22		D40390P		B09		YC056-YD157	
5527	12		CQ		20-6		30-41-12	D40386P		8		D42400P		1		YC051-YC055	
5527	12		CQ		20-3		30-41-12	D40386P		8		D42400P		1		YC056-YN236, YN501-YR323, YR325-YR328	
5528	16		CQ		20-6		30-41-12	D40386P		6		D42400P		2		YC051-YC055	
5528	16		CQ		20-3		30-41-12	D40386P		6		D42400P		2		YC056-YN236, YN501-YR323, YR325-YR328	
5529	20		PA		8-9		SPARE	D40392P		A14		D40390P		A17		YC051-YN236, YN501-YR323, YR325-YR328	
5530	20		PA		8-9		SPARE	D40392P		B14		D40390P		A18		YC051-YD157	
5533	20		PA		20-2		SPARE	D40386P		24		D40388P		A16		YC051-YC055	
5533	20		PA		20-0		SPARE	D40386P		24		D40388P		A16		YC056-YL999, YR301-YR323, YR325-YR328	
5534	20		PA		22-5		SPARE	D40386P		23		D40392P		A18		YC051-YC055	
5534	20		PA		22-4		SPARE	D40386P		23		D40392P		A18		YC056-YL999, YR301-YR323, YR325-YR328	
5535	20		PA		20-10		SPARE	D40386P		29		D40394P		A15		YC051-YC055	
5535	20		PA		20-8		SPARE	D40386P		29		D40394P		A15		YC056-YL999, YR301-YR323, YR325-YR328	
5536	22		PA		4-3		21-25-11	D41010P		13		D40388P		B12		YC051-YC055	
5536	22		PA		4-1		21-25-11	D41010P		13		D40388P		B12		YC056-YN236, YN501-YR323, YR325-YR328	
5538	24		PK		4-3		21-31-24	D40388P		B14		D41010P		23		YC051-YC055	
5538	24		PK		4-1		21-31-24	D40388P		B14		D41010P		23		YC056-YD157	
5539	24		B6		20-4		21-51-25	D41832P		4		D41830P		A02		YC051-YC055	

WIRE LIST

D280A108

91-21-11

Section W6410

Page 11

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6412	286A6412				AP0600B TO E3 AND E4 (RB2) (continued)										
5539	24		B6		19-9	21-51-25	D41832P		4		D41830P	A02			YC056-YL999, YR301-YR323, YR325-YR328
5540	24		PK		19-9	36-21-11	D41010P		4		D40386P	5			YC051-YC055
5540	24		PK		19-2	36-21-11	D41010P		4		D40386P	5			YC056-YN236, YN501-YR323, YR325-YR328
5541	24		B6		20-4	21-61-13	D41832P		15		D41830P	B01			YC051-YC055
5541	24		B6		19-9	21-61-13	D41832P		15		D41830P	B01			YC056-YL999, YR301-YR323, YR325-YR328
5542	24		PK		23-7	21-61-13	D41832P		6		D41822P	A03			YC051-YC055
5542	24		PK		23-5	21-61-13	D41832P		6		D41822P	A03			YC056-YL999, YR301-YR323, YR325-YR328
5543	24		B6		20-4	21-61-14	D41832P		14		D41830P	B02			YC051-YC055
5543	24		B6		19-9	21-61-14	D41832P		14		D41830P	B02			YC056-YL999, YR301-YR323, YR325-YR328
5544	24		PK		23-7	21-61-14	D41832P		8		D41822P	A04			YC051-YC055
5544	24		PK		23-5	21-61-14	D41832P		8		D41822P	A04			YC056-YL999, YR301-YR323, YR325-YR328
5546	24		PK		9-0	31-62-24	D40394P		A04		D40388P	A20			YC051-YC055
5546	24		PK		9-2	31-62-24	D40394P		A04		D40388P	A20			YC056-YN236, YN501-YR323, YR325-YR328
5547	20		PA		22-5	27-31-11	D40386P		30		D40392P	A07			YC051-YC055
5547	20		PA		22-4	27-31-11	D40386P		30		D40392P	A07			YC056-YN236, YN501-YR323, YR325-YR328
5548	24		PK		8-9	SPARE	D40392P		A16		D40390P	B10			YC067-YD157
5548	24		PK		8-9	31-31-17	D40392P		A16		D40390P	B10			YD158-YN236, YN501-YR323, YR325-YR328
6001	24		PK		22-5	77-31-11	D40386P		17		D40392P	B19			YC051-YC055
6001	24		PK		22-4	77-31-11	D40386P		17		D40392P	B19			YC056-YN236, YN501-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W6410

Page 12

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type		Splice
W6412	286A6412				AP0600B TO E3 AND E4 (RB2) (continued)											
6002	24		B6		8-7	80-11-11	D41010P	11			D40394P	A20			YC051-YC055	
6002	24		B6		8-4	80-11-11	D41010P	11			D40394P	A20			YC056-YN236, YN501-YR323, YR325-YR328	
6003	24		B6		8-7	80-11-11	D41010P	12			D40394P	B01			YC051-YC055	
6003	24		B6		8-4	80-11-11	D41010P	12			D40394P	B01			YC056-YN236, YN501-YR323, YR325-YR328	
6004	24		PK		2-11	73-22-11	D40392P	B07			D40394P	B02			YC051-YC055	
6004	24		PK		3-0	73-22-11	D40392P	B07			D40394P	B02			YC056-YN236, YN501-YR323, YR325-YR328	
6005	24		PK		2-11	73-22-31	D40394P	B03			D40392P	B08			YC051-YC055	
6005	24		PK		3-0	73-22-31	D40394P	B03			D40392P	B08			YC056-YN236, YN501-YR323, YR325-YR328	
6006	24		PK		8-9	73-22-31	D40392P	B09			D40390P	B06			YC051-YN236, YN501-YR323, YR325-YR328	
6007	24		PK		2-11	73-23-11	D40392P	B10			D40394P	B04			YC051-YC055	
6007	24		PK		3-0	73-23-11	D40392P	B10			D40394P	B04			YC056-YN236, YN501-YR323, YR325-YR328	
6008	24		PK		2-11	73-23-11	D40392P	B11			D40394P	B05			YC051-YC055	
6008	24		PK		3-0	73-23-11	D40392P	B11			D40394P	B05			YC056-YN236, YN501-YR323, YR325-YR328	
6009	22		PA		2-11	76-21-21	D40392P	B12			D40394P	B06			YC051-YC055	
6009	22		PA		3-0	76-21-21	D40392P	B12			D40394P	B06			YC056-YN236, YN501-YR323, YR325-YR328	
6010	20		PA		22-5	78-36-21	D40386P	15			D40392P	B13			YC051-YC055	
6010	20		PA		22-4	78-36-21	D40386P	15			D40392P	B13			YC056-YN236, YN501-YR323, YR325-YR328	
6011	22		PA		2-11	78-36-21	D40392P	A13			D40394P	B07			YC051-YC055	
6011	22		PA		3-0	78-36-21	D40392P	A13			D40394P	B07			YC056-YN236, YN501-YR323, YR325-YR328	

WIRE LIST

D280A108

91-21-11

Section W6410

Page 13

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To				Effectivity
Wire No.	GA	CO TY	FT-IN		Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W6412	286A6412			AP0600B TO E3 AND E4 (RB2) (continued)											
6012	22	CQ		3-7	SPARE	D40388P	B07		D40390P	B14			YC051-YC055		
6012	22	CQ		3-9	SPARE	D40388P	B07		D40390P	B14			YC056-YD157		
6014	22	CQ		20-3	28-44-11	D40386P	26		D40712P	11			YC051-YC055		
6014	22	CQ		20-0	28-44-11	D40386P	26		D40712P	11			YC056-YN236, YN501-YR323, YR325-YR328		
6016	18	CQ		20-3	28-44-11	D40386P	10		D40712P	20			YC051-YC055		
6016	18	CQ		20-0	28-44-11	D40386P	10		D40712P	20			YC056-YN236, YN501-YR323, YR325-YR328		
6025	20	CQ		20-3	28-44-11	D40386P	25		D40712P	19			YC051-YC055		
6025	20	CQ		20-0	28-44-11	D40386P	25		D40712P	19			YC056-YN236, YN501-YR323, YR325-YR328		
C-A				0-0	52-71-11	S00194	RED		SP01158		9		YC051-YN236, YN501-YR323, YR325-YR328		
C-B				0-0	52-71-11	S00194	BLU		SP01162		9		YC051-YN236, YN501-YR323, YR325-YR328		
C-C				0-0	52-71-11	S00194	YEL		SP01160		9		YC051-YN236, YN501-YR323, YR325-YR328		
W6414	286A6414			AP0600B TO E/E BAY (RB2)											
0002	20	PA		17-10	33-32-11	D11448	2		D40396P	12			YC051-YC055		
0002	20	PA		18-2	33-32-11	D11448	2		D40396P	12			YC056-YR328		
0006	20	PA		19-6	33-36-11	D11448	6		D46142P	A06			YC051-YC055		
0006	20	PA		19-9	33-36-11	D11448	6		D46142P	A06			YC056-YR328		
0009	22	CQ		10-0	21-33-11	D46142P	A09	VP	SP05006		9		YL952, YN232		
0009	22	CQ		10-0	21-33-11	D46142P	A09		SP05006		9		YL953-YL999, YN233-YR328		
0010	22	CQ		10-0	21-33-11	D46142P	A10	VP	SP05008		9		YL952, YN232		
0010	22	CQ		10-0	21-33-11	D46142P	A10		SP05008		9		YL953-YL999, YN233-YR328		
0014	20	PA		17-9	25-29-11	D40396P	5		D11448	14			ALL		
0015	20	PA		8-8	25-29-11	D11448	15		D00152	=P	LD		ALL		
0017	20	PA		19-6	33-36-12	D11448	17		D46142P	A07			YC051-YC055		
0017	20	PA		19-9	33-36-12	D11448	17		D46142P	A07			YC056-YR328		

WIRE LIST

D280A108

91-21-11

Section W6410

Page 14

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6414		286A6414			AP0600B TO E/E BAY (RB2) (continued)											
0051		20		PA		7-5	25-29-11	D00152	=G	LD		GD00408	ST..	1A		ALL
0052		20		PA		7-5	25-29-11	D00152	=N	LD		GD00408	AC..	1A		ALL
0501		22		PA		17-10	24-41-11	D11448			16	D40396P		1		YC051-YC055
0501		22		PA		18-2	24-41-11	D11448			16	D40396P		1		YC056-YR328
0502		24		PK		17-10	SPARE	D11448			4	D40396P		6		YC051-YC055
0502		24		PK		18-2	SPARE	D11448			4	D40396P		6		YC056-YR328
0503		24		PK		17-10	24-32-11	D11448			18	D40396P		2		YC051-YC055
0503		24		PK		18-2	24-32-11	D11448			18	D40396P		2		YC056-YR328
0504		24		PK		17-10	24-32-11	D11448			5	D40396P		8		YC051-YC055
0504		24		PK		18-2	24-32-11	D11448			5	D40396P		8		YC056-YR328
0506		22		PA		17-10	24-23-51	D40396P			9	D11448		20		YC051-YC055
0506		22		PA		18-2	24-23-51	D40396P			9	D11448		20		YC056-YR328
0507		20		PA		17-10	24-32-11	D11448			3	D40396P		3		YC051-YC055
0507		20		PA		18-2	24-32-11	D11448			3	D40396P		3		YC056-YR328
0509		22		PA		19-6	24-28-11	D11448			13	D46142P		A03		YC051-YC055
0509		22		PA		19-9	24-28-11	D11448			13	D46142P		A03		YC056-YR328
0510		22		PA		19-6	24-28-11	D11448			12	D46142P		A04		YC051-YC055
0510		22		PA		19-9	24-28-11	D11448			12	D46142P		A04		YC056-YR328
0514		22		CQ		19-6	29-22-11	D11448			25	D46142P		A05		YC051-YC055
0514		22		CQ		19-9	29-22-11	D11448			25	D46142P		A05		YC056-YR328
0519		20		PA		2-5	24-51-21	D11448			9	GD00408		DC..	1A	ALL
0523		22		PA		19-6	24-22-21	D11448			23	D46142P		A02		YC051-YC055
0523		22		PA		19-9	24-22-21	D11448			23	D46142P		A02		YC056-YR328
5501		24		PK		17-10	21-27-21	D11448			26	D40396P		11		YC051-YC055
5501		24		PK		18-2	21-27-21	D11448			26	D40396P		11		YC056-YR328
5502		20		PA		4-4	21-27-21	D11448			27	D00162		1		ALL
5503		20		PA		4-4	21-27-21	D11448			28	D00162		2		ALL
5504		20		PA		4-4	21-27-21	D11448			29	D00162		3		ALL
5505		20		PA		3-1	21-27-21	D00162			7	GD00408		ST..	1A	ALL
5506		22		PA		4-4	21-27-21	D11448			7	D00162		5		ALL
5507		20		PA		22-6	21-27-21	D00162			6	D46142P		A01		YC051-YC055
5507		20		PA		22-10	21-27-21	D00162			6	D46142P		A01		YC056-YR328
5508		18		PA		17-10	SPARE	D40396P			4	D11448		33		YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W6410

Page 15 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6420	286A6420			E3-3 TO E4-1 (SB2)											
0301	24		PK		10-6	21-51-22	D41810P	A01			D41808P	A01			YC051-YL999, YR301-YR323, YR325-YR328
0302	24		PK		10-6	21-51-22	D41810P	A02			D41808P	A02			YC051-YL999, YR301-YR323, YR325-YR328
0303	24		PK		10-6	21-51-22	D41810P	A03			D41808P	A03			YC051-YL999, YR301-YR323, YR325-YR328
0304	24		PK		10-6	21-51-24	D41808P	A04			D41810P	A04			YC051-YL999, YR301-YR323, YR325-YR328
0305	24		PK		10-6	21-51-24	D41808P	A05			D41810P	A05			YC051-YL999, YR301-YR323, YR325-YR328
0306	24		PK		10-6	21-51-24	D41808P	A06			D41810P	A06			YC051-YL999, YR301-YR323, YR325-YR328
0307	24		PK		10-6	21-51-24	D41808P	A07			D41810P	A07			YC051-YL999, YR301-YR323, YR325-YR328
0308	24		PK		10-6	21-51-24	D41808P	A08			D41810P	A08			YC051-YL999, YR301-YR323, YR325-YR328
0309	22		PA		11-3	21-61-15	D41810P	A09			D41802P	A09			YC051-YL999, YR301-YR323, YR325-YR328
0401	24		PK		10-6	21-61-13	D41810P	B01			D41808P	B01			YC051-YL999, YR301-YR323, YR325-YR328
0402	24		PK		10-6	21-61-13	D41810P	B02			D41808P	B02			YC051-YL999, YR301-YR323, YR325-YR328
0403	24		PK		10-6	21-61-13	D41810P	B03			D41808P	B03			YC051-YL999, YR301-YR323, YR325-YR328
0404	24		PK		10-6	21-61-13	D41810P	B04			D41808P	B04			YC051-YL999, YR301-YR323, YR325-YR328

WIRE LIST
D280A108

91-21-11
Section W6420
Page 1
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W6420	286A6420				E3-3 TO E4-1 (SB2) (continued)											
0405	24		PK		10-6		21-61-13	D41810P	B05			D41808P	B05			YC051-YL999, YR301-YR323, YR325-YR328
0406	24		PK		10-6		21-61-14	D41810P	B06			D41808P	B06			YC051-YL999, YR301-YR323, YR325-YR328
0407	24		PK		10-6		21-61-14	D41810P	B07			D41808P	B07			YC051-YL999, YR301-YR323, YR325-YR328
0408	24		PK		10-6		21-61-14	D41808P	B08			D41810P	B08			YC051-YL999, YR301-YR323, YR325-YR328
0409	24		PK		10-6		21-61-14	D41810P	B09			D41808P	B09			YC051-YL999, YR301-YR323, YR325-YR328
0410	24		PK		10-6		21-61-14	D41810P	B10			D41808P	B10			YC051-YL999, YR301-YR323, YR325-YR328
W6424	286A6424				P92 TO P6 & P18											
0001	08		CQ		16-8		24-61-24	D11440	A			TB5060G	7	E		YC051-YC055
0001	08		CQ		16-9		24-61-24	D11440	A			TB5060G	7	E		YC056-YR328
0002	10		CQ		28-1		24-61-23	D11440	C			TB5180D	1	E		YC051-YC055
0002	10		CQ		28-2		24-61-23	D11440	C			TB5180D	1	E		YC056-YR328
0003	08		CQ		16-5		24-51-21	D11442	A			TB5060G	1	E		YC051-YC055
0003	08		CQ		16-6		24-51-24	D11442	A			TB5060G	1	E		YC056-YC070, YD160-YR328
0003	08		CQ		16-6		24-51-21	D11442	A			TB5060G	1	E		YD151-YD158
0004	08		CQ		16-5		24-51-21	D11442	B			TB5060G	2	E		YC051-YC055
0004	08		CQ		16-6		24-51-24	D11442	B			TB5060G	2	E		YC056-YC070, YD160-YR328
0004	08		CQ		16-6		24-51-21	D11442	B			TB5060G	2	E		YD151-YD158
0005	08		CQ		16-5		24-51-21	D11442	C			TB5060G	3	E		YC051-YC055
0005	08		CQ		16-6		24-51-24	D11442	C			TB5060G	3	E		YC056-YC070, YD160-YR328
0005	08		CQ		16-6		24-51-21	D11442	C			TB5060G	3	E		YD151-YD158
0006	10		CQ		16-5		24-51-21	D11442	G			TB5060G	4	E		YC051-YC055
0006	10		CQ		16-6		24-51-22	D11442	G			TB5060G	4	E		YC056-YC070, YD160-YR328

WIRE LIST

D280A108

91-21-11

Section W6420

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W6424	286A6424				P92 TO P6 & P18 (continued)											
0006	10		CQ		16-6	24-51-21	D11442		G			TB5060G	4	E		YD151-YD158
0007	10		CQ		16-6	24-51-21	D11442		E			TB5060G	5	E		YC051-YC055
0007	10		CQ		16-7	24-51-22	D11442		E			TB5060G	5	E		YC056-YC070, YD160-YR328
0007	10		CQ		16-7	24-51-21	D11442		E			TB5060G	5	E		YD151-YD158
0008	10		CQ		16-6	24-51-21	D11442		D			TB5060G	6	E		YC051-YC055
0008	10		CQ		16-7	24-51-22	D11442		D			TB5060G	6	E		YC056-YC070, YD160-YR328
0008	10		CQ		16-7	24-51-21	D11442		D			TB5060G	6	E		YD151-YD158
0009	10		CQ		28-0	24-51-21	D11444		A			TB5180D	2	E		YC051-YC055
0009	10		CQ		28-1	24-51-23	D11444		A			TB5180D	2	E		YC056-YC070, YD160-YR328
0009	10		CQ		28-1	24-51-21	D11444		A			TB5180D	2	E		YD151-YD158
0010	10		CQ		28-1	24-51-21	D11444		B			TB5180D	3	E		YC051-YC055
0010	10		CQ		28-2	24-51-23	D11444		B			TB5180D	3	E		YC056-YC070, YD160-YR328
0010	10		CQ		28-2	24-51-21	D11444		B			TB5180D	3	E		YD151-YD158
0011	10		CQ		28-2	24-51-21	D11444		C			TB5180D	4	E		YC051-YC055
0011	10		CQ		28-3	24-51-23	D11444		C			TB5180D	4	E		YC056-YC070, YD160-YR328
0011	10		CQ		28-3	24-51-21	D11444		C			TB5180D	4	E		YD151-YD158
0012	08		CQ		3-2	24-51-21	D11444		G			GD00920	AC..	F		ALL
0016	08		CQ		16-11	24-51-25	D11444		F			TB5060L	10	E		YL951-YR328
0017	08		CQ		16-11	24-51-25	D11444		E			TB5060L	11	E		YL951-YR328
0018	08		CQ		16-10	24-51-25	D11444		D			TB5060L	12	E		YL951-YR328

WIRE LIST

D280A108

91-21-11
Section W6420
Page 3 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I	W6430	286A6430			P92 TO EQUIPMENT COOLING SUPPLY FAN (RB2)											
I	5501	20		CQ		3-4	21-27-31	D11802		2		D03470		1		ALL
I	5502	20		CQ		3-4	21-27-31	D11802		3		D03470		2		ALL
I	5503	20		CQ		3-4	21-27-31	D11802		4		D03470		3		ALL
I	5504	20		PA		3-0	21-27-31	D03470		7		GD00408	ST..	1A		ALL
I	5505	22		CQ		3-4	21-27-31	D11802		6		D03470		5		ALL
I	5506	20		CQ		3-9	21-27-31	D03470		6		SP02004		S		ALL

WIRE LIST

D280A108

91-21-11

Section W6430

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6491	286A6491				WEATHER RADAR SCOPE, CONT, R/T										
0001	20		PA		1-8	34-41-11	D00189C		9		D02273		A		YC051-YC055
0001	20		PA		1-11	34-41-11	D00189C		9		D02273		A		YC056-YD158, YL951-YR328
0002	20		CQ		14-9	34-41-11	D02273		C		D40107P		B01		YC051-YC052
0002	20		CQ		19-10	34-41-11	D02273		C		D40147P		10		YC053-YC055
0002	20		CQ		20-3	34-41-11	D02273		C		D40147P		10		YC056-YD158, YL951-YR328
0003	20		PA		2-6	34-41-11	D02273		E		GD00383		AC..	1A	YC051-YC055
0003	20		PA		2-9	34-41-11	D02273		E		GD00383		AC..	1A	YC056-YD158, YL951-YR328
0005	22		PA		17-11	34-41-11	D00189B		G14		D40089P		A08		YC051-YC052
0005	22		PA		17-10	34-41-11	D00189B		G14		TB1808X		B002	1A	YC053-YD158, YL951-YR328
0006	22		PA		19-9	34-41-11	D00189B		B09		D40147P		25		YC053-YC055
0006	22		PA		19-11	34-41-11	D00189B		B09		D40147P		25		YC056-YD158, YL951-YR328
0007	24		PK		0-7	34-41-11	D00189B		F03		SM00001			9	YC053-YC058
0007	24		PK		0-7	34-41-11	D00189B		F03		SM00002			9	YC059-YD158, YL951-YR328
0008	24		PK		18-3	34-41-11	D00189B		D08		D00193		D		YC051-YD158, YL951-YR328
0009	24		PK		18-3	34-41-11	D00189B		B06		D00193		V		YC051-YD158, YL951-YR328
0010	24		PK		18-3	34-41-11	D00189B		E06		D00193		U		YC051-YD158, YL951-YR328
0011	24		PK		18-3	34-41-11	D00189B		E07		D00193		F-		YC051-YD158, YL951-YR328
0012	24		PK		18-3	34-41-11	D00189B		D07		D00193		M		YC051-YD158, YL951-YR328
0013	22		PA		10-10	34-41-11	D00193		G		D40089P		A07		YC051-YC052
0013	22		PA		28-8	34-41-11	D00193		G		D40149P		A08		YC053-YC055
0013	22		PA		28-6	34-41-11	D00193		G		D40149P		A08		YC056-YD158, YL951-YR328
0014	20		PA		4-0	34-41-11	D00193		A		GD00813		DC..	1A	YC051-YD158, YL951-YR328
0015	22		PA		19-9	34-41-11	D00189B		B10		D40147P		26		YC053-YC055
0015	22		PA		19-11	34-41-11	D00189B		B10		D40147P		26		YC056-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W6490

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY	Fam FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W6491	286A6491	WEATHER RADAR SCOPE, CONT, R/T (continued)			
0016	20 PA	2-3 34-41-11	D00189C 7	GD00383 AC.. 1A	YC051-YD158, YL951-YR328
0017	20 PA	2-3 34-41-11	D00189C 11	GD00383 DC.. 1A	YC051-YD158, YL951-YR328
0018	20 CQ	14-6 34-41-11	D00189C 2	D40107P B02	YC051-YC052
0018	20 CQ	19-8 34-41-11	D00189C 2	D40147P 11	YC053-YC055
0018	20 CQ	19-10 34-41-11	D00189C 2	D40147P 11	YC056-YD158, YL951-YR328
0019	24 PK	18-3 34-41-11	D00189B C06	D00193 K	YC051-YD158, YL951-YR328
0020	24 PK	18-3 34-41-11	D00189B D06	D00193 L	YC051-YD158, YL951-YR328
0021	22 PA	17-11 34-41-11	D00189B F01	D40091P A04	YC051-YC052
0022	22 PA	17-11 34-41-11	D00189B D01	D40091P A03	YC051-YC052
0022	24 PK	19-9 34-41-11	D00189B D01	D40147P 27	YC053-YC055
0022	24 PK	19-11 34-41-11	D00189B D01	D40147P 27	YC056-YD158, YL951-YR328
0023	22 PA	14-7 34-41-11	D00189B F15 VP	D40107P B06	YC051-YC052
0023	22 PA	29-3 34-41-11	D00189B F15	D40149P B07	YC053-YC055
0023	22 PA	29-1 34-41-11	D00189B F15	D40149P B07	YC056-YD158, YL951-YR328
0024	22 PA	14-7 34-41-11	D00189B F14 VP	D40107P B07	YC051-YC052
0024	22 PA	29-3 34-41-11	D00189B F14	D40149P B08	YC053-YC055
0024	22 PA	29-1 34-41-11	D00189B F14	D40149P B08	YC056-YD158, YL951-YR328
0025	24 PK	0-7 34-41-11	D00189B G01	SM00001 9	YC051-YC052
0025	24 PK	0-7 34-41-11	D00189B F04	SM00001 9	YL951-YR328
0026	24 PK	0-7 34-41-11	D00189B F07	SM00001 9	YC051-YD158, YL951-YR328
0027	24 PK	0-7 34-41-11	D00189B D09	SM00001 9	YC051-YD158, YL951-YR328
0028	24 PK	0-7 34-41-11	D00189B C04	SM00001 9	YC051-YC052
0028	24 PK	0-7 34-41-11	D00189B E09	SM00001 9	YC053-YD158, YL951-YR328
0029	24 PK	0-7 34-41-11	D00189B A02	SM00001 9	YC051-YC052
0029	24 PK	0-7 34-41-11	D00189B E01	SM00001 9	YC053-YC058
0029	24 PK	0-7 34-41-11	D00189B E01	SM00002 9	YC059-YD158, YL951-YR328
0030	24 PK	0-7 34-41-11	D00189B A03	SM00001 9	YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W6490

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6491	286A6491				WEATHER RADAR SCOPE, CONT, R/T (continued)										
0030	24		PK		0-7	34-41-11	D00189B	G01			SM00001		9		YC053-YC058
0030	24		PK		0-7	34-41-11	D00189B	G01			SM00002		9		YC059-YD158, YL951-YR328
0031	24		PK		17-11	34-41-11	D00189B	B11	VP		D40091P	A05			YC051-YC052
0032	24		PK		14-7	34-41-11	D00189B	B12	VP		D40107P	B05			YC051-YC052
0033	24		PK		17-10	34-53-11	D00189B	B09	VP		TB1806Y	A009	1A		YC051-YC052
0034	24		PK		19-9	34-49-11	D00189B	F01			D40147P	23			YC053-YC055
0034	24		PK		19-11	34-49-11	D00189B	F01			D40147P	23			YC056-YD158, YL951-YR328
0035	22		PA		14-7	34-41-11	D00189B	E02			D40107P	B10			YC051-YC052
0035	22		PA		19-9	34-41-11	D00189B	E02			D40147P	1			YC053-YC055
0035	22		PA		19-11	34-41-11	D00189B	E02			D40147P	1			YC056-YD158, YL951-YR328
0036	22		PA		17-11	34-41-11	D00189B	B14			D40091P	A06			YC051-YC052
0036	22		PA		19-9	34-41-11	D00189B	B14			D40147P	2			YC053-YC055
0036	22		PA		19-11	34-41-11	D00189B	B14			D40147P	2			YC056-YD158, YL951-YR328
0040	24		PK		0-7	34-41-11	D00189B	F02			SM00001		9		YC053-YD158, YL951-YR328
0041	20		PA		2-4	34-41-11	D00189B			FD	GD00383	ST..	1A		YC051-YD158, YL951-YR328
0042	20		PA		3-10	34-41-11	D00193			FC	GD00815	ST..	1A		YC051-YD158, YL951-YR328
0043	20		PA		1-5	34-41-11	D01411	29			GD00449	ST..	E	*1	YC051-YD158, YL951-YR328
0044	20		PA		1-4	34-41-11	D01411	28			GD00459	DC..	E		YC051-YD158, YL951-YR328
0045	24		PK		14-7	34-53-21	D00189B	B10	VP		D40107P	A07			YC051-YC052
0046	24		PK		0-7	34-41-11	D00189B	D10			SM00001		9		YC053-YC058
0046	24		PK		0-7	34-41-11	D00189B	D10			SM00002		9		YC059-YD158, YL951-YR328
0047	24		PK		17-11	34-41-11	D00189B	K10			D40091P	A07			YC051-YC052
0047	24		PK		19-9	34-41-11	D00189B	K10			D40147P	13			YC053-YC055
0047	24		PK		19-11	34-41-11	D00189B	K10			D40147P	13			YC056-YD158, YL951-YR328
0048	22		GK		19-9	34-41-11	D00189B	J02			D40147P	28			YC053-YC055
0048	22		GK		19-11	34-41-11	D00189B	J02			D40147P	28			YC056-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W6490

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W6491	286A6491	WEATHER RADAR SCOPE, CONT, R/T (continued)													
0050	20	PA	1-5	34-41-11	D01411	18			GD00449	ST..	E			YC051-YD158, YL951-YR328	
0051	20	PA	1-5	34-41-11	D01411	3			GD00449	ST..	E	*1		YC051-YD158, YL951-YR328	
0052	20	PA	1-5	34-41-11	D01411	15			GD00449	ST..	E	*1		YC051-YD158, YL951-YR328	
0053	20	PA	1-5	34-41-11	D01411	11			GD00449	ST..	E	*2		YC051-YD158, YL951-YR328	
0054	20	PA	1-5	34-41-11	D01411	35			GD00449	ST..	E	*2		YC051-YD158, YL951-YR328	
0055	20	PA	1-5	34-41-11	D01411	32			GD00449	ST..	E	*2		YC051-YD158, YL951-YR328	
0057	20	PA	1-5	34-41-11	D01411	21			GD00449	ST..	E	*2		YC051-YD158, YL951-YR328	
0058	20	PA	2-4	34-41-11	D00189B			FB	GD00383	ST..	1A			YC051-YD158, YL951-YR328	
0059	20	PA	2-3	34-41-11	D00189C			FE	GD00383	ST..	1A			YC051-YD158, YL951-YR328	
0060	20	PA	2-4	34-41-11	D00189B			FF	GD00383	ST..	1A			YC051-YD158, YL951-YR328	
0061	20	PA	2-4	34-41-11	D00189B			FG	GD00383	ST..	1A			YC051-YD158, YL951-YR328	
0062	20	PA	2-4	31-62-13	D00189B			FH	GD00383	ST..	1A			YC051-YC052	
0062	20	PA	2-4	31-62-15	D00189B			FH	GD00383	ST..	1A			YC053-YD158, YL951-YR328	
0063	20	PA	2-4	31-62-23	D00189B			FJ	GD00383	ST..	1A			YC051-YC052	
0063	20	PA	2-4	31-62-25	D00189B			FJ	GD00383	ST..	1A			YC053-YD158, YL951-YR328	
0064	20	PA	2-4	34-21-13	D00189B			FK	GD00383	ST..	1A			YC051-YD158, YL951-YR328	
0065	20	PA	2-4	34-21-23	D00189B			FL	GD00383	ST..	1A			YC051-YD158, YL951-YR328	
0097	24	PK	0-7	34-41-11	SM00001		9		SM00002			9		YC059-YD158, YL951-YR328	
0098	24	PK	0-7	34-41-11	D00189B	A03			SM00002			9		YC059-YD158, YL951-YR328	
0099	24	PK	0-7	34-41-11	D00189B	A04			SM00002			9		YC059-YD158, YL951-YR328	

WIRE LIST

D280A108

91-21-11

Section W6490

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6491	286A6491				WEATHER RADAR SCOPE, CONT, R/T (continued)										
1001	24	Y1	W		4-2	34-41-11	D00189B	D11			D01411	27			YC051-YD158, YL951-YR328
1001Z			W		0-0	34-41-11	D00189B			FD	GD00451	ST..	E	*3	YC051-YD158, YL951-YR328
2001B	20	X2	AA		4-1	34-41-11	D00189C	8			D01411	26			YC051-YD158, YL951-YR328
2001R	20	X2	AA		0-0	34-41-11	D00189C	3			D01411	25			YC051-YD158, YL951-YR328
2001Z			AA		0-0	34-41-11	D00189C			FE	GD00451	ST..	E	*1	YC051-YD158, YL951-YR328
2002B	24	Y2	AB		4-2	34-41-11	D00189B	C14			D01411	4			YC051-YD158, YL951-YR328
2002R	24	Y2	AB		0-0	34-41-11	D00189B	C13			D01411	5			YC051-YD158, YL951-YR328
2002Z			AB		0-0	34-41-11	D00189B			FD	GD00451	ST..	E	*1	YC051-YD158, YL951-YR328
2003B	24	Y2	AC		4-2	34-41-11	D00189B	E14			D01411	16			YC051-YD158, YL951-YR328
2003R	24	Y2	AC		0-0	34-41-11	D00189B	E13			D01411	17			YC051-YD158, YL951-YR328
2003Z			AC		0-0	34-41-11	D00189B			FD	GD00451	ST..	E	*1	YC051-YD158, YL951-YR328
2004B	24	Y2	AD		4-2	34-41-11	D00189B	A14			D01411	9			YC051-YD158, YL951-YR328
2004R	24	Y2	AD		0-0	34-41-11	D00189B	A13			D01411	10			YC051-YD158, YL951-YR328
2004Z			AD		0-0	34-41-11	D00189B			FD	GD00451	ST..	E	*1	YC051-YD158, YL951-YR328
2005B	24	Y2	AE		4-2	34-41-11	D00189B	D15			D01411	33			YC051-YD158, YL951-YR328
2005R	24	Y2	AE		0-0	34-41-11	D00189B	E15			D01411	34			YC051-YD158, YL951-YR328
2005Z			AE		0-0	34-41-11	D00189B			FD	GD00451	ST..	E	*2	YC051-YD158, YL951-YR328
2006B	24	Y2	AF		4-2	34-41-11	D00189B	B15			D01411	30			YC051-YD158, YL951-YR328
2006R	24	Y2	AF		0-0	34-41-11	D00189B	A15			D01411	31			YC051-YD158, YL951-YR328

WIRE LIST
D280A108

91-21-11
Section W6490
Page 5
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From				To				Effectivity
	GA	CO	TY			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W6491	286A6491			WEATHER RADAR SCOPE, CONT, R/T (continued)										
2006Z				AF	0-0 34-41-11	D00189B			FD	GD00451	ST..	E	*2	YC051-YD158, YL951-YR328
2007B	24	7K	AM		17-11 34-41-11	D00189B	D03			D40089P	A10			YC051-YC052
2007B	24	7K	AM		19-9 34-41-11	D00189B	D03			D40147P	7			YC053-YC055
2007B	24	7K	AM		19-11 34-41-11	D00189B	D03			D40147P	7			YC056-YD158, YL951-YR328
2007W	24	7K	AM		0-0 34-41-11	D00189B	D02			D40089P	A09			YC051-YC052
2007W	24	7K	AM		0-0 34-41-11	D00189B	D02			D40147P	6			YC053-YD158, YL951-YR328
2007Z			AM		0-0 34-41-11	D00189B			FF	D40089P	PERG	1F		YC051-YC052
2007Z			AM		0-0 34-41-11	D00189B			FF	D40147P			AM	YC053-YD158, YL951-YR328
2008B	24	Y2	AG		17-11 31-62-13	D00189B	B04			D40089P	A02			YC051-YC052
2008B	24	Y2	AG		29-3 31-62-15	D00189B	B04			D40149P	B02			YC053-YC055
2008B	24	Y2	AG		29-1 31-62-15	D00189B	B04			D40149P	B02			YC056-YD158, YL951-YR328
2008R	24	Y2	AG		0-0 31-62-13	D00189B	B03			D40089P	A01			YC051-YC052
2008R	24	Y2	AG		0-0 31-62-15	D00189B	B03			D40149P	B01			YC053-YD158, YL951-YR328
2008Z			AG		0-0 31-62-13	D00189B			FH	D40089P	PERG	1F		YC051-YC052
2008Z			AG		0-0 31-62-15	D00189B			FH	D40149P	PERG	1F		YC053-YD158, YL951-YR328
2009B	24	7K	AQ		14-7 34-41-11	D00189B	G03			D40107P	B04			YC051-YC052
2009B	24	7K	AQ		19-9 34-41-11	D00189B	G03			D40147P	12			YC053-YC055
2009B	24	7K	AQ		19-11 34-41-11	D00189B	G03			D40147P	12			YC056-YD158, YL951-YR328
2009W	24	7K	AQ		0-0 34-41-11	D00189B	G02			D40107P	B03			YC051-YC052
2009W	24	7K	AQ		0-0 34-41-11	D00189B	G02			D40147P	9			YC053-YD158, YL951-YR328
2009Z			AQ		0-0 34-41-11	D00189B			FG	D40107P	PERG	1F		YC051-YC052
2009Z			AQ		0-0 34-41-11	D00189B			FG	D40147P			AQ	YC053-YD158, YL951-YR328
2010B	24	Y2	AN		14-7 31-62-23	D00189B	J04			D40107P	A02			YC051-YC052
2010B	24	Y2	AN		29-3 31-62-25	D00189B	J04			D40149P	A10			YC053-YC055
2010B	24	Y2	AN		29-1 31-62-25	D00189B	J04			D40149P	A10			YC056-YD158, YL951-YR328
2010R	24	Y2	AN		0-0 31-62-23	D00189B	J03			D40107P	A01			YC051-YC052
2010R	24	Y2	AN		0-0 31-62-25	D00189B	J03			D40149P	A09			YC053-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W6490

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To			Effectivity				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6491	286A6491			WEATHER RADAR SCOPE, CONT, R/T (continued)											
2010Z				AN	0-0	31-62-23	D00189B			FJ	D40107P	PERG	1F		YC051-YC052
2010Z				AN	0-0	31-62-25	D00189B			FJ	D40149P	PERG	1F		YC053-YD158, YL951-YR328
2011B	24	Y2	AR		18-3	34-41-11	D00189B	B08			D00193	J-			YC051-YD158, YL951-YR328
2011R	24	Y2	AR		0-0	34-41-11	D00189B	B07			D00193	H-			YC051-YD158, YL951-YR328
2011Z				AR	0-0	34-41-11	D00189B			FB	D00193			FC	YC051-YD158, YL951-YR328
2012B	24	Y2	H		17-11	34-21-13	D00189B	J12			D40089P	A04			YC051-YC052
2012B	24	Y2	H		29-3	34-21-13	D00189B	J12			D40149P	B12			YC053-YC055
2012B	24	Y2	H		29-1	34-21-13	D00189B	J12			D40149P	B12			YC056-YD158, YL951-YR328
2012R	24	Y2	H		0-0	34-21-13	D00189B	J11			D40089P	A03			YC051-YC052
2012R	24	Y2	H		0-0	34-21-13	D00189B	J11			D40149P	B11			YC053-YD158, YL951-YR328
2012Z				H	0-0	34-21-13	D00189B			FK	D40089P	PERG	1F		YC051-YC052
2012Z				H	0-0	34-21-13	D00189B			FK	D40149P	PERG	1F		YC053-YD158, YL951-YR328
2013B	24	Y2	AP		14-7	34-21-23	D00189B	G13			D40107P	A04			YC051-YC052
2013B	24	Y2	AP		29-3	34-21-23	D00189B	G13			D40149P	B04			YC053-YC055
2013B	24	Y2	AP		29-1	34-21-23	D00189B	G13			D40149P	B04			YC056-YD158, YL951-YR328
2013R	24	Y2	AP		0-0	34-21-23	D00189B	G12			D40107P	A03			YC051-YC052
2013R	24	Y2	AP		0-0	34-21-23	D00189B	G12			D40149P	B03			YC053-YD158, YL951-YR328
2013Z				AP	0-0	34-21-23	D00189B			FL	D40107P	PERG	1F		YC051-YC052
2013Z				AP	0-0	34-21-23	D00189B			FL	D40149P	PERG	1F		YC053-YD158, YL951-YR328
2014B	24	Y2	BA		29-1	34-61-14	D00189B	B01			D40149P	A04			YL951-YR328
2014R	24	Y2	BA		0-0	34-61-14	D00189B	A01			D40149P	A03			YL951-YR328
2014Z				BA	0-0	34-61-14	D00189B	DED			D40149P	PERG	1F		YL951-YR328
2015B	24	Y2	AV		17-11	34-41-11	D00189B	C02	VP		D40091P	A02			YC051-YC052
2015B	24	Y2	AV		29-3	34-41-11	D00189B	C02			D40149P	A02			YC053-YC055
2015B	24	Y2	AV		29-1	34-41-11	D00189B	C02			D40149P	A02			YC056-YD158, YL951-YR328
2015R	24	Y2	AV		0-0	34-41-11	D00189B	C01	VP		D40091P	A01			YC051-YC052
2015R	24	Y2	AV		0-0	34-41-11	D00189B	C01			D40149P	A01			YC053-YD158, YL951-YR328

WIRE LIST
D280A108

91-21-11
Section W6490
Page 7
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY	Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice
W6491	286A6491	WEATHER RADAR SCOPE, CONT, R/T (continued)			
2015Z		AV	0-0 34-41-11	D00189B DED	D40091P PERG 1F YC051-YC052
2015Z		AV	0-0 34-41-11	D00189B DED	D40149P PERG 1F YC053-YD158, YL951-YR328
2016B	24 Y2	AW	14-7 34-41-11	D00189B A06 VP	D40107P B09 YC051-YC052
2016B	24 Y2	AW	29-3 34-41-11	D00189B A06	D40149P B10 YC053-YC055
2016B	24 Y2	AW	29-1 34-41-11	D00189B A06	D40149P B10 YC056-YD158, YL951-YR328
2016R	24 Y2	AW	0-0 34-41-11	D00189B A05 VP	D40107P B08 YC051-YC052
2016R	24 Y2	AW	0-0 34-41-11	D00189B A05	D40149P B09 YC053-YD158, YL951-YR328
2016Z		AW	0-0 34-41-11	D00189B DED	D40107P PERG 1F YC051-YC052
2016Z		AW	0-0 34-41-11	D00189B DED	D40149P PERG 1F YC053-YD158, YL951-YR328
2017B	24 Y2	AT	17-11 34-21-14	D00189B K12 VP	D40089P A06 YC051-YC052
2017B	24 Y2	AT	29-3 34-21-14	D00189B K12	D40149P B06 YC053-YC055
2017B	24 Y2	AT	29-1 34-21-14	D00189B K12	D40149P B06 YC056-YD158, YL951-YR328
2017R	24 Y2	AT	0-0 34-21-14	D00189B K11 VP	D40089P A05 YC051-YC052
2017R	24 Y2	AT	0-0 34-21-14	D00189B K11	D40149P B05 YC053-YD158, YL951-YR328
2017Z		AT	0-0 34-21-14	D00189B DED	D40089P PERG 1F YC051-YC052
2017Z		AT	0-0 34-21-14	D00189B DED	D40149P PERG 1F YC053-YD158, YL951-YR328
2018B	24 Y2	AU	14-7 34-21-24	D00189B J10 VP	D40107P A06 YC051-YC052
2018B	24 Y2	AU	29-3 34-21-24	D00189B J10	D40149P A06 YC053-YC055
2018B	24 Y2	AU	29-1 34-21-24	D00189B J10	D40149P A06 YC056-YD158, YL951-YR328
2018R	24 Y2	AU	0-0 34-21-24	D00189B J09 VP	D40107P A05 YC051-YC052
2018R	24 Y2	AU	0-0 34-21-24	D00189B J09	D40149P A05 YC053-YD158, YL951-YR328
2018Z		AU	0-0 34-21-24	D00189B DED	D40107P PERG 1F YC051-YC052
2018Z		AU	0-0 34-21-24	D00189B DED	D40149P PERG 1F YC053-YD158, YL951-YR328
2019B	20 PB	A	4-0 33-11-41	D00193 E-	GD00805 AC.. 1A YC051-YD158, YL951-YR328
2019R	20 PB	A	0-0 33-11-41	D00193 P	TB0801W A013 1 YC051-YD158, YL951-YR328
2020B	24 7K	AH	30-2 34-41-11	D40147P 16	D40149P A12 YC053-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W6490

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Description Fam FT-IN Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W6491	286A6491			WEATHER RADAR SCOPE, CONT, R/T (continued)									
2020W	24	7K	AH	0-0 34-41-11	D40147P	15			D40149P	A11			YC053-YD158, YL951-YR328
2020Z			AH	0-0 34-41-11	D40147P			AH	D40149P	PERG	1F		YC053-YD158, YL951-YR328
2021B	24	7K	AI	30-2 34-41-11	D40147P	19			D40149P	B14			YC053-YD158, YL951-YR328
2021W	24	7K	AI	0-0 34-41-11	D40147P	18			D40149P	B13			YC053-YD158, YL951-YR328
2021Z			AI	0-0 34-41-11	D40147P			AI	D40149P	PERG	1F		YC053-YD158, YL951-YR328
2022B	24	Y2	AO	19-9 34-49-11	D00189B	J06			D40147P	22			YC053-YC055
2022B	24	Y2	AO	19-11 34-49-11	D00189B	J06			D40147P	22			YC056-YD158, YL951-YR328
2022R	24	Y2	AO	0-0 34-49-11	D00189B	J05			D40147P	21			YC053-YD158, YL951-YR328
2022Z			AO	0-0 34-49-11	D00189B	DED			D40147P			AO	YC053-YD158, YL951-YR328
2201B	24	M5	AS	17-10 34-41-11	D00189B	K09			TB1808X	B001	1A		YC051-YD158, YL951-YR328
2201R	24	M5	AS	0-0 34-41-11	D00189B	K08			TB1808X	A001	1A		YC051-YD158, YL951-YR328
2201ZI			AS	0-0 34-41-11	D00189B	DED			TB1808X	A002	1A		YC051-YD158, YL951-YR328
2201ZO			AS	0-0 34-41-11	D00189B	DED			GB01808	ST..	1A		YC051-YD158, YL951-YR328
3001B	24	Y3	AJ	4-2 34-41-11	D00189B	C11			D01411	8			YC051-YD158, YL951-YR328
3001R	24	Y3	AJ	0-0 34-41-11	D00189B	C10			D01411	2			YC051-YD158, YL951-YR328
3001Y	24	Y3	AJ	0-0 34-41-11	D00189B	C12			D01411	19			YC051-YD158, YL951-YR328
3001Z			AJ	0-0 34-41-11	D00189B			FD	GD00451	ST..	E	*2	YC051-YD158, YL951-YR328
3002B	24	Y3	AK	4-2 34-41-11	D00189B	E11			D01411	13			YC051-YD158, YL951-YR328
3002R	24	Y3	AK	0-0 34-41-11	D00189B	E10			D01411	14			YC051-YD158, YL951-YR328
3002Y	24	Y3	AK	0-0 34-41-11	D00189B	E12			D01411	12			YC051-YD158, YL951-YR328

WIRE LIST
D280A108

91-21-11
Section W6490
Page 9
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice		
W6491	286A6491				WEATHER RADAR SCOPE, CONT, R/T (continued)											
3002Z				AK	0-0	34-41-11	D00189B				FD	GD00451	ST..	E	*2	YC051-YD158, YL951-YR328
3003B	24	Y3	AL		4-2	34-41-11	D00189B		A11			D01411	37			YC051-YD158, YL951-YR328
3003R	24	Y3	AL		0-0	34-41-11	D00189B		A10			D01411	20			YC051-YD158, YL951-YR328
3003Y	24	Y3	AL		0-0	34-41-11	D00189B		A12			D01411	36			YC051-YD158, YL951-YR328
3003Z				AL	0-0	34-41-11	D00189B				FD	GD00451	ST..	E	*3	YC051-YD158, YL951-YR328
FRAA					0-0	34-41-11	D40147P				AM	D40147P	S/R			YC053-YD158, YL951-YR328
FRAB					0-0	34-41-11	D40147P				AQ	D40147P	S/R			YC053-YD158, YL951-YR328
FRAC					0-0	34-41-11	D40147P				AH	D40147P	S/R			YC053-YD158, YL951-YR328
FRAD					0-0	34-41-11	D40147P				AI	D40147P	S/R			YC053-YD158, YL951-YR328
FRAH					0-0	34-41-11	D40147P		14			D40147P			AH	YC053-YD158, YL951-YR328
FRAI					0-0	34-41-11	D40147P		17			D40147P			AI	YC053-YD158, YL951-YR328
FRAM					0-0	34-41-11	D40147P		5			D40147P			AM	YC053-YD158, YL951-YR328
FRAO					0-0	34-49-11	D40147P		20			D40147P			AO	YC053-YD158, YL951-YR328
FRAQ					0-0	34-41-11	D40147P		8			D40147P			AQ	YC053-YD158, YL951-YR328
FRAX					0-0	34-49-11	D40147P				AO	D40147P	S/R			YC053-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W6490

Page 10 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6502	286A6502				RIGHT A/C PACK (STA 536R) DISC TO A/C PACK (SB2)										
0001	20		HA		4-1	33-33-11	D41600	10			L00184	=P	BK		YC051-YL999, YR301-YR328
0001	20		HA		3-8	33-33-11	D41600	10			L00184	=P	BK		YN231-YN501
0002	20		HA		3-4	33-33-11	L00184	=G	G7		GD06522	AC..	GW		YC051-YD157
0002	20		HA		3-5	33-33-11	L00184	=G	G7		GD06522	AC..	GW		YD158-YL999, YR301-YR328
0002	20		HA		2-0	33-33-11	L00184	=G	G7		GD00562	AC..	GW		YN231-YN501
1001	20		HE	AA	5-0	21-42-11	D00490	2			D41600	8			YC051-YD152
1001Z				AA	0-0	21-42-11	GD02360	ST..	GW	*1	D41600	S/R			YC051-YD152
1002R	20		H9	AB	7-2	26-12-11	D41600	9			M01910	=B	GW		ALL
1002Z				AB	0-0	26-12-11	D41600	S/R			GD06526	ST..	GW	*1	YC051-YL999, YR301-YR328
1002Z				AB	0-0	26-12-11	D41600	S/R			GD00076	DC..	GW	*1	YN231-YN501
1003R	20		H9	AC	3-9	26-12-11	M01910	=A	GW		D00846	=1			ALL
1003Z				AC	0-0	26-12-11	GD06526	ST..	GW	*1	GD02356	ST..	GW		YC051-YL999, YR301-YR328
1003Z				AC	0-0	26-12-11	GD00076	DC..	GW	*1	GD02356	ST..	GW		YN231-YN501
1004	20		HE	AD	5-0	21-51-21	D00490	3			D41600	3			YC051-YD152
1004Z				AD	0-0	21-51-21	GD02360	ST..	GW	*1	D41600	S/R			YC051-YD152
1005	20		HE	AE	3-0	21-51-21	D00490	1			GD06524	DC..	GW	*1	YC051-YD152
1005Z				AE	0-0	21-51-21	GD02360	ST..	GW	*1	GD06524	DC..	GW	*1	YC051-YD152
1006	20		HE	AF	3-8	21-51-21	D00492	3			GD06524	DC..	GW	*2	YC051-YD157
1006	20		HE	AF	3-7	21-51-21	D00492	3			GD06524	DC..	GW	*2	YD158-YL999, YR301-YR328
1006	20		HE	AF	4-0	21-51-21	D00492	3			GD00398	DC..	GW	*1	YN231-YN501
1006Z				AF	0-0	21-51-21	GD02358	ST..	GW	*1	GD06524	DC..	GW	*2	YC051-YL999, YR301-YR328
1006Z				AF	0-0	21-51-21	GD02358	ST..	GW	*1	GD00398	DC..	GW	*1	YN231-YN501
1007	20		HE	AG	5-3	21-51-21	D41600	5			D00964	1			YC051-YD157
1007	20		HE	AG	5-1	21-51-21	D41600	5			D00964	1			YD158-YR328
1007Z				AG	0-0	21-51-21	D41600	S/R			GD02358	ST..	GW	*1	ALL
1008	20		HE	AH	3-3	21-51-21	D00964	2			GD06524	DC..	GW	*3	YC051-YD157
1008	20		HE	AH	3-2	21-51-21	D00964	2			GD06524	DC..	GW	*3	YD158-YL999, YR301-YR328
1008	20		HE	AH	3-7	21-51-21	D00964	2			GD00398	DC..	GW	*2	YN231-YN501
1008Z				AH	0-0	21-51-21	GD02358	ST..	GW	*1	GD06524	DC..	GW	*3	YC051-YL999, YR301-YR328
1008Z				AH	0-0	21-51-21	GD02358	ST..	GW	*1	GD00398	DC..	GW	*2	YN231-YN501

WIRE LIST

D280A108

91-21-11
Section W6500
Page 1
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W6502	286A6502	RIGHT A/C PACK (STA 536R) DISC TO A/C PACK (SB2) (continued)			
1009	20 HE AI	5-1 21-61-15	D41600 11	D03914 1	YC051-YL999, YR301-YR328
1009Z	AI	0-0 21-61-15	D41600 S/R	GD06524 DC.. GW	YC051-YL999, YR301-YR328
1013	20 HE AM	2-8 21-51-21	D40846P 1	GD06524 DC.. GW *2	YD153-YD157
1013	20 HE AM	3-1 21-51-21	D40846P 1	GD06524 DC.. GW *2	YD158-YL999, YR301-YR328
1013	20 HE AM	6-1 21-51-21	D40846P 1	GD00076 DC.. GW *2	YN231-YN501
1013Z	AM	0-0 21-51-21	D40846P S/R	GD06524 DC.. GW *2	YD153-YL999, YR301-YR328
1013Z	AM	0-0 21-51-21	D40846P S/R	GD00076 DC.. GW *2	YN231-YN501
1014	20 HE AN	3-2 21-42-11	D40846P 2	D41600 8	YD153-YD157, YN231-YN501
1014	20 HE AN	2-11 21-42-11	D40846P 2	D41600 8	YD158-YL999, YR301-YR328
1014Z	AN	0-0 21-42-11	D40846P S/R	D41600 S/R	YD153-YR328
1015	20 HE AP	3-2 21-51-21	D40846P 3	D41600 3	YD153-YD157, YN231-YN501
1015	20 HE AP	2-11 21-51-21	D40846P 3	D41600 3	YD158-YL999, YR301-YR328
1015Z	AP	0-0 21-51-21	D40846P S/R	D41600 S/R	YD153-YR328
2001B	20 HF GA	5-5 21-51-21	D00394 1	D41600 2	YC051-YD157
2001B	20 HF GA	5-4 21-51-21	D00394 1	D41600 2	YD158-YR328
2001R	20 HF GA	0-0 21-51-21	D00394 2	D41600 1	ALL
2001Z	GA	0-0 21-51-21	GD02358 ST.. GW *2	D41600 S/R	ALL
2002B	20 HF GB	6-2 21-51-21	D00492 1	D41600 4	YC051-YD157
2002B	20 HF GB	6-1 21-51-21	D00492 1	D41600 4	YD158-YR328
2002R	20 HF GB	0-0 21-51-21	D00492 5	D41600 6	ALL
2002Z	GB	0-0 21-51-21	GD02358 ST.. GW *2	D41600 S/R	ALL
5501	20 HA	4-6 21-61-15	D03914 2	GD02358 ST.. GW	YC051-YD157
5501	20 HA	4-5 21-61-15	D03914 2	GD02358 ST.. GW	YD158-YL999, YR301-YR328
5519	20 HA	2-9 21-61-15	D03914 3	GD06524 DC.. GW *3	YC051-YD152, YD158-YL999, YR301-YR328
5519	20 HA	2-10 21-61-15	D03914 3	GD06524 DC.. GW *3	YD153-YD157
W6504	286A6504	RIGHT A/C PACK (STA 536R) DISC TO A/C PACK (SB2)			
1001	20 HE AA	3-10 21-51-21	D00490 1	D40846J 1	YD153-YD157

WIRE LIST

D280A108

91-21-11

Section W6500

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W6504	286A6504	RIGHT A/C PACK (STA 536R) DISC TO A/C PACK (SB2) (continued)													
1001	20	HE	AA	3-9	21-51-21	D00490	1		D40846J	1				YD158-YR328	
1001Z			AA	0-0	21-51-21	GD02360	ST..	GW	*1	D40846J	S/R			YD153-YR328	
1002	20	HE	AB	3-10	21-42-11	D00490	2		D40846J	2				YD153-YD157	
1002	20	HE	AB	3-9	21-42-11	D00490	2		D40846J	2				YD158-YR328	
1002Z			AB	0-0	21-42-11	GD02360	ST..	GW	*1	D40846J	S/R			YD153-YR328	
1003	20	HE	AC	3-10	21-51-21	D00490	3		D40846J	3				YD153-YD157	
1003	20	HE	AC	3-9	21-51-21	D00490	3		D40846J	3				YD158-YR328	
1003Z			AC	0-0	21-51-21	GD02360	ST..	GW	*1	D40846J	S/R			YD153-YR328	
W6506	286A6506	P8 TO E/E BAY													
0500	22	PA		9-11	34-41-11	D11132	18		D46106P	5				YC053-YC065	
0500	22	PA		9-8	34-41-11	D11132	18		D46106P	5				YC067-YR328	
0501	20	CQ		13-8	49-62-11	D40812P	7		D00580	5				ALL	
0502	20	CQ		4-11	49-62-11	D00580	4		TB0803X	B002	1A			ALL	
0506	20	PA		13-8	29-11-11	D00578	25		D40812P	3				ALL	
0507	20	PA		14-7	29-11-11	D00578	26		D46132P	A01				ALL	
0508	20	PA		14-7	29-11-11	D00578	24		D46132P	A02				ALL	
0515	24	PK		14-3	29-33-11	D00578	19		D46106P	4				ALL	
0516	24	PK		14-7	29-33-11	D00578	20		D46106P	3				ALL	
0517	22	CQ		9-11	27-62-11	D11132	1		D46106P	11				YC051-YC065	
0517	22	CQ		9-8	27-62-11	D11132	1		D46106P	11				YC067-YR328	
0526	22	PA		9-11	31-53-11	D11132	16		D46106P	7				YC051-YC065	
0526	22	PA		9-8	31-53-11	D11132	16		D46106P	7				YC067-YR328	
0540	22	PA		6-0	31-53-11	D11132	17		GD00813	DC..	1A			YC051-YC065	
0540	22	PA		5-3	31-53-11	D11132	17		GD00813	DC..	1A			YC067-YR328	
0557	22	PA		9-11	32-64-21	D11132	3		D46106P	8				YC051-YC065	
0557	22	PA		9-8	32-64-21	D11132	3		D46106P	8				YC067-YR328	
0558	22	PA		9-11	32-64-21	D11132	24		D46106P	9				YC051-YC065	
0558	22	PA		9-8	32-64-21	D11132	24		D46106P	9				YC067-YR328	
0559	22	PA		6-0	32-64-21	D11132	2		GD00813	DC..	1A			YC051-YC065	
0559	22	PA		5-3	32-64-21	D11132	2		GD00813	DC..	1A			YC067-YR328	
0560	22	PA		6-0	32-64-21	D11132	23		GD00813	DC..	1A			YC051-YC065	
0560	22	PA		5-3	32-64-21	D11132	23		GD00813	DC..	1A			YC067-YR328	
1303	20	X1	EQ	14-2	74-11-11	D11292	12		D46132P	A05				ALL	
1303Z			EQ	0-0	74-11-11	D11292	S/R		D46132P	PERG	1F			ALL	
2201B	22	PB	KA	14-3	24-22-21	D00578	17		D46106P	1				ALL	
2201R	22	PB	KA	0-0	24-22-21	D00578	16		D46106P	2				ALL	
2202B	22	X2	KB	11-2	24-22-31	D00580	16		D48132P	A03				ALL	
2202R	22	X2	KB	0-0	24-22-31	D00580	17		D48132P	A02				ALL	

WIRE LIST

D280A108

91-21-11

Section W6500

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6506		286A6506			P8 TO E/E BAY (continued)											
2202Z					KB	0-0	24-22-31	D00580		DED		D48132P		DED		ALL
5501	24	PK				13-8	36-11-11	D40812P	18			D00578	10			ALL
5502	24	PK				14-3	36-11-11	D46106P	17			D00578	11			ALL
5503	24	PK				14-3	36-11-11	D46106P	18			D00578	9			ALL
5504	20	PA				13-7	33-18-63	D40812P	4			D01080	4			ALL
5505	20	PA				13-7	33-18-63	D40812P	5			D01080	10			ALL
5506	20	PA				4-5	33-18-63	D01080	6			TB0804Z	A021	1A		ALL
5507	20	PA				4-6	33-18-63	D00578	2			TB0804Z	A021	1A		ALL
5508	20	PA				4-6	33-18-63	D00580	2			TB0804Z	A021	1A		ALL
5509	20	PA				4-9	31-52-45	D01080	7			TB0804Y	A005	1A		ALL
5510	24	PK				13-0	21-27-21	D40812P	19			D48138P	A01			ALL
6001R	20	PH				4-3	26-11-31	D01080	16			GD00813	DC..	1A		ALL
6002R	20	PH				4-11	26-11-31	D00580	1			TB0804X	A001	1A		ALL
6003R	20	PH				4-11	26-11-31	D00580	27			TB0804X	B001	1A		ALL
6004R	20	PH				4-4	26-11-31	D00580	28			GD00813	DC..	1A		ALL
6005	24	B6				13-11	76-21-21	D11292	5			D46106P	12			ALL
6006	24	B6				13-11	76-21-21	D11292	4			D46106P	13			ALL
6007	20	PA				3-5	76-21-21	D11292	15			GD00809	DC..	1A		ALL
6008	20	CQ				13-8	28-21-11	D00578	22			D40812P	9			ALL
6009	20	PA				6-1	28-21-11	D00578	23			D11292	9			ALL
6010	20	CQ				4-8	28-21-11	D00578	21			TB0803Y	B013	1A		ALL
6011	20	PA				2-10	28-21-11	D11292	7			TB0803Y	B013	1A		ALL
6012	20	PA				14-2	28-21-11	D11292	8			D46132P	A04			ALL
6013	20	PA				13-4	28-21-11	D46132P	A03			TB0803Y	B013	1A		ALL
6014	20	PA				13-8	78-34-21	D00578	5			D40812P	10			ALL
6015	20	PA				8-8	78-34-21	D00578	6			SP00968		S		ALL
6025	18	PA				9-7	78-32-61	D40812P	6	18		TB0606V	A015	1		ALL
6026	22	PA				11-5	78-32-61	D11132	7			TB0606V	A015	1		YC051-YC065
6026	22	PA				11-2	78-32-61	D11132	7			TB0606V	A015	1		YC067-YR328
6027	20	PA				13-4	74-11-11	D11292	11			D40812P	11			ALL
6028	20	CQ				13-8	76-21-21	D00578	30			D40812P	12			ALL
6029R	20	9P				4-8	76-21-21	D00578	31			TB0804X	B015	1A		ALL
6030	20	CQ				14-3	76-21-21	D00578	29			D46106P	14			ALL
6031R	22	PH				9-1	26-11-21	D40812P	13			SM00016		W		ALL
6032R	22	PH				10-5	26-11-21	D40810P	19			SM00016		W		ALL
6033R	22	PH				5-1	26-11-21	D01080	31			SM00016		W		ALL
6034R	22	PH				15-0	26-11-21	D01080	17			D40810P	26			ALL
6035R	22	PH				15-0	26-11-21	D01080	28			D40810P	27			ALL
6036R	22	PH				15-0	26-11-21	D01080	24			D40810P	28			ALL

WIRE LIST

D280A108

91-21-11

Section W6500

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From			To					
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6506	286A6506			P8 TO E/E BAY (continued)											
6037R	22		PH		15-0	26-11-21	D01080		19		D40810P	30			ALL
6038R	22		PH		15-0	26-11-21	D01080		18		D40810P	29			ALL
6039R	22		PH		1-6	26-11-21	D01080		20		D00578	27			ALL
6040R	22		PH		1-6	26-11-21	D01080		21		D00578	1			ALL
6041R	22		PH		13-0	26-21-11	D40812P		14		D48138P	A07			ALL
6042R	22		PH		11-1	26-21-11	D01080		13		D48138P	A02			ALL
6043R	22		PH		11-1	26-21-11	D01080		8		D48138P	A03			ALL
6044R	22		PH		11-1	26-21-11	D01080		25		D48138P	A08			ALL
6045R	22		PH		5-1	26-21-11	D01080		9		SM00038		W		ALL
6046R	22		PH		9-1	26-21-11	D40812P		15		SM00038		W		ALL
6047R	22		PH		5-2	26-21-11	D00580		14		SM00038		W		ALL
6048R	22		PH		5-2	26-21-11	D00580		8		SM00038		W		ALL
6049R	22		PH		11-2	26-21-11	D00578		12		D48138P	A09			ALL
6050R	22		PH		11-2	26-21-11	D00578		14		D48138P	A04			ALL
6051R	22		PH		11-2	26-21-11	D00578		4		D48138P	A05			ALL
6052R	22		PH		11-2	26-21-11	D00578		8		D48138P	A06			ALL
6053R	22		PH		15-0	26-21-11	D01080		2		D40810P	20			ALL
6054R	22		PH		11-1	26-21-11	D01080		11		D48138P	B04			ALL
6055R	22		PH		11-1	26-21-11	D01080		27		D48138P	B02			ALL
6066R	22		PH		5-1	26-21-11	D01080		30		SM00006		W		ALL
6067R	22		PH		5-1	26-21-11	D01080		1		SM00010		W		ALL
6068R	22		PH		15-0	26-21-11	D01080		3		D40810P	22			ALL
6069R	22		PH		11-2	26-21-11	D00578		18		D48138P	B05			ALL
6070R	22		PH		11-2	26-21-11	D00578		3		D48138P	B06			ALL
6071R	22		PH		11-2	26-21-11	D00578		7		D48138P	B07			ALL
6072R	22		PH		5-2	26-21-11	D00578		13		SM00006		W		ALL
6073R	22		PH		5-2	26-21-11	D00580		3		SM00010		W		ALL
6074R	22		PH		10-5	26-21-11	D40810P		24		SM00006		W		ALL
6075R	22		PH		10-5	26-21-11	D40810P		25		SM00038		W		ALL
6077	20		PA		9-2	78-35-21	D40812P		16		D10169	2			YC051-YC065
6077	20		PA		9-1	78-35-21	D40812P		16		D10169	2			YC067-YR328
6078	20		PA		11-2	78-35-21	D10169		3		TB0606Y	A007	1A		ALL
6079	20		PA		5-2	78-35-21	D10169		1		GD00815	ST..	1A		YC051-YC065
6079	20		PA		5-1	78-35-21	D10169		1		GD00815	ST..	1A		YC067-YR328
6080R	22		PH		10-2	26-21-11	D40810P		33		D48138P	B01			ALL
6081R	22		PH		10-2	26-21-11	D40810P		34		D48138P	B03			ALL
6082R	22		PH		15-0	26-21-11	D40810P		35		D01080	15			ALL
6083R	22		PH		10-5	26-21-11	D40810P		21		SM00010		W		ALL
6084R	22		PH		4-4	26-11-21	D00578		28		GD00813	DC..	1A		ALL

WIRE LIST

D280A108

91-21-11

Section W6500

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6506		286A6506			P8 TO E/E BAY (continued)											
6085		22		PA		6-1	30-11-11	D11132				D48132P	A05			YC051-YC065
6085		22		PA		6-7	30-11-11	D11132				D48132P	A05			YC067-YR328
6086		22		PA		6-0	30-11-11	D11132				GD00813	DC..	1A		YC051-YC065
6086		22		PA		5-3	30-11-11	D11132				GD00813	DC..	1A		YC067-YR328
6087		22		PA		13-0	28-41-11	D40812P				D48132P	A04			ALL
6088		22		PA		9-11	78-32-61	D11132				D46106P	15			YC051-YC065
6088		22		PA		9-8	78-32-61	D11132				D46106P	15			YC067-YR328
6089		22		PA		9-11	78-32-61	D11132				D46106P	16			YC051-YC065
6089		22		PA		9-8	78-32-61	D11132				D46106P	16			YC067-YR328

WIRE LIST

D280A108

91-21-11

Section W6500

Page 6 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I W6510	286A6510			P8 TO E/E BAY AND J BOX											
0004	22		PA		40-0	21-27-21	D40694P	19			SP00471		9		YC060-YC064
0005	22		PA		40-0	21-27-21	D40694P	28			SP00469		9		YC060-YC064
0006	22		PA		20-0	21-27-21	D40696P	26			SP00480		9		YC060-YC064
0007	22		PA		20-0	21-27-21	D40696P	25			D00164	6			YC060-YC064
0012	22		PA		8-3	31-35-03	D40696P	28			SP00779		S		YN236-YR328
1301	20		X1	EN	15-3	74-11-11	D11290	12			D46118P	A05			YC051-YD158, YL951-YR328
1301Z				EN	0-0	74-11-11	D11290	S/R			D46118P	PERG	1F		YC051-YD158, YL951-YR328
1311	20		X1	EY	9-3	73-22-11	D40696P	3			D46118P	B01			YC051-YD158, YL951-YR328
1311Z				EY	0-0	73-22-11	D40696P			EN	D46118P	PERG	1F		YC051-YD158, YL951-YR328
2601B	24		Y2	SA	9-3	73-21-11	D40696P	2			D46118P	A02			YC051-YD158, YL951-YR328
2601R	24		Y2	SA	0-0	73-21-11	D40696P	1			D46118P	A01			YC051-YD158, YL951-YR328
2601Z				SA	0-0	73-21-11	D40696P			SK	D46118P	PERG	1F		YC051-YD158, YL951-YR328
5502	24		PK		14-7	21-27-21	D40696P	13			D48130P	A02			YC051-YD158, YL951-YR328
5503	24		PK		14-7	21-27-21	D40696P	11			D48130P	A03			YC051-YD158, YL951-YR328
5504	24		PK		14-7	21-27-21	D40696P	15			D48130P	A01			YC051-YD158, YL951-YR328
6001	20		PA		15-3	74-11-11	D11290	11			D46118P	A07			YC051-YD158, YL951-YR328
6002	20		CQ		2-3	76-21-21	D11290	9			TB0804X	B015	1A		YC051-YD158, YL951-YR328
6003	20		CQ		15-3	76-21-21	D11290	7			D46118P	A10			YC051-YD158, YL951-YR328
6004	24		B6		15-3	76-21-21	D11290	8			D46118P	B09			YC051-YD158, YL951-YR328
6005	24		PK		14-7	76-21-21	D11290	5			D40696P	5			YC051-YD158, YL951-YR328
6006	24		PK		14-7	76-21-21	D11290	4			D40696P	6			YC051-YD158, YL951-YR328
6007	20		PA		2-9	76-21-21	D11290	15			GD00809	DC..	1A		YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W6510

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6510		286A6510			P8 TO E/E BAY AND J BOX (continued)											
6009		22		CQ		14-7	21-27-21	D40696P	25			D48130P	A09			YL951-YR328
6010		22		CQ		14-7	21-27-21	D40696P	26			D48130P	A10			YL951-YR328
6011		20		PA		9-3	73-22-11	D40696P	4			D46118P	B02			YC051-YD158, YL951-YR328
6012		24		PK		9-3	73-22-31	D40696P	7			D46118P	A04			YC051-YD158, YL951-YR328
6013		24		PK		9-3	76-21-21	D40696P	8			D46118P	A08			YC051-YD158, YL951-YR328
6030		20		PA		14-7	78-34-21	D10173	5			D40696P	21			YC051-YD158, YL951-YR328
6031		20		PA		8-3	78-34-21	D10173	4			SP00968		S		YC051-YD158, YL951-YR328
FREF						0-0	73-22-11	D40696P	S/R			D40696P			EN	YC051-YD158, YL951-YR328
FREG						0-0	73-22-11	D40696P	10			D40696P			EN	YC051-YD158, YL951-YR328
FRSF						0-0	73-21-11	D40696P	9			D40696P			SK	YC051-YD158, YL951-YR328
FRSG						0-0	73-21-11	D40696P	S/R			D40696P			SK	YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W6510

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6528	286A6528				DISC AB0500DR TO E1-3, E1-4, E4-1 (SB2)										
0001	20		PA		6-1	33-33-11	D41602		10		D04582P		4		YC051-YL999, YR301-YR328
0001	20		PA		5-5	33-33-11	D41602		10		D04582P		4		YN231-YN501
0301	20		PA		38-1	21-51-25	D43044P		A04		D03942		2		YC051-YC055
0301	20		PA		38-0	21-51-25	D43044P		A04		D03942		2		YC056-YL999, YR301-YR328
0302	24		PK		38-5	21-61-13	D43044P		B08		D04582P		8		YC051-YC055
0302	24		PK		38-4	21-61-13	D43044P		B08		D04582P		8		YC056-YL999, YR301-YR328
0303	24		PK		38-5	21-61-13	D43044P		B09		D04582P		9		YC051-YC055
0303	24		PK		38-4	21-61-13	D43044P		B09		D04582P		9		YC056-YL999, YR301-YR328
0304	24		PK		38-5	21-61-13	D43044P		B10		D04582P		10		YC051-YC055
0304	24		PK		38-4	21-61-13	D43044P		B10		D04582P		10		YC056-YL999, YR301-YR328
0305	24		PK		38-5	21-61-14	D43044P		A05		D04582P		11		YC051-YC055
0305	24		PK		38-4	21-61-14	D43044P		A05		D04582P		11		YC056-YL999, YR301-YR328
0306	24		PK		38-5	21-61-14	D43044P		A06		D04582P		12		YC051-YC055
0306	24		PK		38-4	21-61-14	D43044P		A06		D04582P		12		YC056-YL999, YR301-YR328
0307	24		PK		38-5	21-61-14	D43044P		B06		D04582P		13		YC051-YC055
0307	24		PK		38-4	21-61-14	D43044P		B06		D04582P		13		YC056-YL999, YR301-YR328
0308	24		PK		38-8	21-61-15	D43044P		B05		D41602		11		YC051-YC055
0308	24		PK		38-6	21-61-15	D43044P		B05		D41602		11		YC056-YL999, YR301-YR328
0309	20		PA		1-10	21-51-25	D03942		1		GD03254	DC..	1A		YC051-YL999, YR301-YR328
0501	22		PA		49-6	32-42-11	D43040P		10		D40406J		1		YC051-YC055
0501	22		PA		49-5	32-42-11	D43040P		10		D40406J		1		YC056-YL999, YR301-YR328
0501	22		PA		39-7	32-42-11	D43040P		10		D40406J		1		YN231-YN501
0502	22		PA		49-6	32-42-11	D43040P		11		D40406J		2		YC051-YC055
0502	22		PA		49-5	32-42-11	D43040P		11		D40406J		2		YC056-YL999, YR301-YR328
0502	22		PA		39-7	32-42-11	D43040P		11		D40406J		2		YN231-YN501
0521	22		PA		27-9	29-32-11	D43044P		A07		D40410J		1		YC051-YC055

WIRE LIST

D280A108

91-21-11

Section W6520

Page 1

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W6528	286A6528				DISC AB0500DR TO E1-3, E1-4, E4-1 (SB2) (continued)											
0521	22		PA		27-8	29-32-11	D43044P	A07			D40410J	1			YC056-YL999, YR301-YR328	
0521	22		PA		17-10	29-32-11	D43044P	A07			D40410J	1			YN231-YN501	
0522	22		PA		27-9	29-32-11	D43044P	B07			D40410J	2			YC051-YC055	
0522	22		PA		27-8	29-32-11	D43044P	B07			D40410J	2			YC056-YL999, YR301-YR328	
0522	22		PA		17-10	29-32-11	D43044P	B07			D40410J	2			YN231-YN501	
0523	22		PA		60-7	27-83-11	D43040P	22			D04582P	3			YC051-YL999, YR301-YR328	
0523	22		CQ		50-4	27-83-11	D43040P	22			D04582P	3			YN231-YN501	
0591	22		PA		49-6	32-41-11	D43040P	12			D40406J	3			YC051-YC055	
0591	22		PA		49-5	32-41-11	D43040P	12			D40406J	3			YC056-YL999, YR301-YR328	
0591	22		PA		39-7	32-41-11	D43040P	12			D40406J	3			YN231-YN501	
1301	20		X1	EN	19-6	74-11-11	D46136P	A07			D43044P	A08			YC051-YC055	
1301	20		X1	EN	19-3	74-11-11	D46136P	A07			D43044P	A08			YC056-YR328	
1301Z				EN	0-0	74-11-11	D46136P	PERG	1F		D43044P	PERG	1F		ALL	
2203B	22		X2	KC	49-6	32-42-11	D43040P	19			D40406J	5			YC051-YC055	
2203B	22		X2	KC	49-5	32-42-11	D43040P	19			D40406J	5			YC056-YL999, YR301-YR328	
2203B	22		X2	KC	39-7	32-42-11	D43040P	19			D40406J	5			YN231-YN501	
2203R	22		X2	KC	0-0	32-42-11	D43040P	18			D40406J	4			ALL	
2203Z				KC	0-0	32-42-11	D43040P	20			D40406J	6			ALL	
2204B	22		PB	KD	49-6	32-42-11	D43040P	17			D40406J	8			YC051-YC055	
2204B	22		PB	KD	49-5	32-42-11	D43040P	17			D40406J	8			YC056-YL999, YR301-YR328	
2204B	22		PB	KD	39-7	32-42-11	D43040P	17			D40406J	8			YN231-YN501	
2204R	22		PB	KD	0-0	32-42-11	D43040P	16			D40406J	7			ALL	
2211B	22		X2	KK	49-6	32-41-11	D43040P	2			D40410J	4			YC051-YC055	
2211B	22		X2	KK	49-5	32-41-11	D43040P	2			D40410J	4			YC056-YL999, YR301-YR328	
2211B	22		X2	KK	39-7	32-41-11	D43040P	2			D40410J	4			YN231-YN501	
2211R	22		X2	KK	0-0	32-41-11	D43040P	1			D40410J	3			ALL	
2211Z				KK	0-0	32-41-11	D43040P	3			D40410J	5			ALL	
2223B	22		PB	KX	43-3	32-64-12	D46136P	A06			D40410J	7			YC051-YC055	
2223B	22		PB	KX	43-2	32-64-12	D46136P	A06			D40410J	7			YC056-YL999, YR301-YR328	
2223B	22		PB	KX	33-4	32-64-12	D46136P	A06			D40410J	7			YN231-YN501	
2223R	22		PB	KX	0-0	32-64-12	D46136P	A05			D40410J	6			ALL	

WIRE LIST

D280A108

91-21-11

Section W6520

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6528	286A6528				DISC AB0500DR TO E1-3, E1-4, E4-1 (SB2) (continued)										
2224B	22	PB	KY		43-3	32-64-12	D46136P	A04			D40410J	9			YC051-YC055
2224B	22	PB	KY		43-2	32-64-12	D46136P	A04			D40410J	9			YC056-YL999, YR301-YR328
2224B	22	PB	KY		33-4	32-64-12	D46136P	A04			D40410J	9			YN231-YN501
2224R	22	PB	KY		0-0	32-64-12	D46136P	A03			D40410J	8			ALL
2241B	22	PB	LQ		43-3	32-31-12	D46136P	A02			D40410J	11			YC051-YC055
2241B	22	PB	LQ		43-2	32-31-12	D46136P	A02			D40410J	11			YC056-YL999, YR301-YR328
2241B	22	PB	LQ		33-4	32-31-12	D46136P	A02			D40410J	11			YN231-YN501
2241R	22	PB	LQ		0-0	32-31-12	D46136P	A01			D40410J	10			ALL
5501	24	PK			38-8	21-51-21	D43044P	A01			D41602	1			YC051-YC055
5501	24	PK			38-6	21-51-21	D43044P	A01			D41602	1			YC056-YL999, YR301-YR328
5501	24	PK			28-10	21-51-21	D43044P	A01			D41602	1			YN231-YN501
5502	24	PK			38-8	21-51-21	D43044P	B01			D41602	2			YC051-YC055
5502	24	PK			38-6	21-51-21	D43044P	B01			D41602	2			YC056-YL999, YR301-YR328
5502	24	PK			28-10	21-51-21	D43044P	B01			D41602	2			YN231-YN501
5503	24	PK			38-8	21-51-21	D43044P	A02			D41602	3			YC051-YC055
5503	24	PK			38-6	21-51-21	D43044P	A02			D41602	3			YC056-YL999, YR301-YR328
5503	24	PK			28-10	21-51-21	D43044P	A02			D41602	3			YN231-YN501
5504	24	PK			38-8	21-51-21	D43044P	B02			D41602	4			YC051-YC055
5504	24	PK			38-6	21-51-21	D43044P	B02			D41602	4			YC056-YL999, YR301-YR328
5504	24	PK			28-10	21-51-21	D43044P	B02			D41602	4			YN231-YN501
5505	24	PK			38-8	21-51-21	D43044P	A03			D41602	5			YC051-YC055
5505	24	PK			38-6	21-51-21	D43044P	A03			D41602	5			YC056-YL999, YR301-YR328
5505	24	PK			28-10	21-51-21	D43044P	A03			D41602	5			YN231-YN501
5506	24	PK			38-8	21-51-21	D43044P	B03			D41602	6			YC051-YC055
5506	24	PK			38-6	21-51-21	D43044P	B03			D41602	6			YC056-YL999, YR301-YR328
5506	24	PK			28-10	21-51-21	D43044P	B03			D41602	6			YN231-YN501
5507	20	PA			32-11	21-51-25	D43044P	A04			D00540	2			YN231-YN501
5509	22	PA			38-8	21-42-11	D43044P	B04			D41602	8			YC051-YC055
5509	22	PA			38-6	21-42-11	D43044P	B04			D41602	8			YC056-YL999, YR301-YR328
5509	22	PA			28-10	21-42-11	D43044P	B04			D41602	8			YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W6520

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice			
W6528	286A6528				DISC AB0500DR TO E1-3, E1-4, E4-1 (SB2) (continued)												
5510	24		PK		38-5		21-51-25	D43044P	A09			D04582P	5			YC051-YC055	
5510	24		PK		38-4		21-51-25	D43044P	A09			D04582P	5			YC056-YL999, YR301-YR328	
5510	24		PK		28-7		21-51-25	D43044P	A09			D04582P	5			YN231-YN501	
5511	24		PK		38-5		21-51-25	D43044P	A10			D04582P	7			YC051-YC055	
5511	24		PK		38-4		21-51-25	D43044P	A10			D04582P	7			YC056-YL999, YR301-YR328	
5511	24		PK		28-7		21-51-25	D43044P	A10			D04582P	7			YN231-YN501	
5512	20		PA		5-4		21-51-25	D00540	1			GD03872	DC..	1		YN231-YN501	
5513	22		PA		49-6		31-31-15	D43040P	23			D40406J	9			YC051-YC055	
5513	22		PA		49-5		31-31-15	D43040P	23			D40406J	9			YC056-YL999, YR301-YR328	
5513	22		PA		39-7		31-31-15	D43040P	23			D40406J	9			YN231-YN501	
6001R	20		PH		49-6		26-12-11	D43040P	14			D40410J	14			YC051-YC055	
6001R	20		PH		49-5		26-12-11	D43040P	14			D40410J	14			YC056-YL999, YR301-YR328	
6001R	20		PH		39-7		26-12-11	D43040P	14			D40410J	14			YN231-YN501	
6002R	20		PH		60-7		26-12-11	D43040P	15			D04582P	2			YC051-YL999, YR301-YR328	
6002R	20		PH		50-4		26-12-11	D43040P	15			D04582P	2			YN231-YN501	
6003R	18		9P		62-10		26-12-11	D43040P	21	18		D00848	=1			YC051-YC055	
6003R	18		9P		62-9		26-12-11	D43040P	21	18		D00848	=1			YC056-YL999, YR301-YR328	
6003R	18		9P		53-4		26-12-11	D43040P	21	18		D00848	=1			YN231-YN501	
6004R	20		PH		6-1		26-12-11	D41602	9			D04582P	1			YC051-YL999, YR301-YR328	
6004R	20		PH		5-5		26-12-11	D41602	9			D04582P	1			YN231-YN501	

WIRE LIST

D280A108

91-21-11

Section W6520

Page 4 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6530	286A6530			DISC AB0500DR TO E3-2 SHELF.											
0507	20		PA		31-1	29-11-11	D43046P	A01			D40400J	1			YC051-YL999, YR301-YR328
0507	20		PA		20-9	29-11-11	D43046P	A01			D40400J	1			YN231-YN501
0508	20		PA		31-1	29-11-11	D43046P	B01			D40400J	2			YC051-YL999, YR301-YR328
0508	20		PA		20-9	29-11-11	D43046P	B01			D40400J	2			YN231-YN501
0517	22		PA		31-1	29-33-11	D43046P	A02			D40400J	5			YC051-YL999, YR301-YR328
0517	22		PA		20-9	29-33-11	D43046P	A02			D40400J	5			YN231-YN501
0518	22		PA		31-1	29-33-11	D43046P	B02			D40400J	6			YC051-YL999, YR301-YR328
0518	22		PA		20-9	29-33-11	D43046P	B02			D40400J	6			YN231-YN501
1101	22	X1		BN	31-1	31-62-24	D43046P	A03			D40400J	3			YC051-YL999, YR301-YR328
1101	22	X1		BN	20-9	31-62-24	D43046P	A03			D40400J	3			YN231-YN501
1101Z				BN	0-0	31-62-24	D43046P	PERG	1F		D40400J	DED			ALL

WIRE LIST

D280A108

91-21-11

Section W6530

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6564	286A6564				RIGHT WING BODY PRESS SEAL TO E/E BAY										
2601B	20	VG	SA		33-1	SPARE	D39910	6			D40158P	A02			YC051-YC055
2601B	20	VG	SA		32-7	SPARE	D39910	6			D40158P	A02			YC056-YL999, YR301-YR328
2601B	20	VG	SA		22-7	SPARE	D39910	6			D40158P	A02			YN231-YN501
2601R	20	VG	SA		0-0	SPARE	D39910	5			D40158P	B02			ALL
2601Z			SA		0-0	SPARE	D39910	S/R			D40158P	PERG	1F		ALL
2602B	24	Y2	SB		33-1	77-12-21	D39910	3			D40158P	A08			YC051-YC055
2602B	24	Y2	SB		32-7	77-12-21	D39910	3			D40158P	A08			YC056-YL999, YR301-YR328
2602B	24	Y2	SB		22-7	77-12-21	D39910	3			D40158P	A08			YN231-YN501
2602R	24	Y2	SB		0-0	77-12-21	D39910	4			D40158P	B08			ALL
2602Z			SB		0-0	77-12-21	D39910	S/R			D40158P	PERG	1F		ALL
2603B	24	PL	SC		33-1	76-21-21	D39910	8			D40158P	A03			YC051-YC055
2603B	24	PL	SC		32-7	76-21-21	D39910	8			D40158P	A03			YC056-YL999, YR301-YR328
2603B	24	PL	SC		22-7	76-21-21	D39910	8			D40158P	A03			YN231-YN501
2603R	24	PL	SC		0-0	76-21-21	D39910	9			D40158P	B03			ALL
6001	20	PA			33-1	80-11-11	D39910	7			D40158P	A04			YC051-YC055
6001	20	PA			32-7	80-11-11	D39910	7			D40158P	A04			YC056-YL999, YR301-YR328
6001	20	PA			22-7	80-11-11	D39910	7			D40158P	A04			YN231-YN501
6002	24	PK			33-1	80-11-11	D39910	11			D40158P	B04			YC051-YC055
6002	24	PK			32-7	80-11-11	D39910	11			D40158P	B04			YC056-YL999, YR301-YR328
6002	24	PK			22-7	80-11-11	D39910	11			D40158P	B04			YN231-YN501
6005	20	PA			33-1	76-21-21	D39910	10			D40158P	A05			YC051-YC055
6005	20	PA			32-7	76-21-21	D39910	10			D40158P	A05			YC056-YL999, YR301-YR328
6005	20	PA			22-7	76-21-21	D39910	10			D40158P	A05			YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W6560

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6570	286A6570			RIGHT WING BODY PRESS SEAL TO RADAR BAY											
1301	20	C2	EN		57-8	28-41-11	D39914	17			D11306	8			YC051-YC055
1301	20	C2	EN		58-1	28-41-11	D39914	17			D11306	8			YC056-YL999, YR301-YR328
1301	20	C2	EN		47-5	28-41-11	D39914	17			D11306	8			YN231-YN501
1301ZI			EN		0-0	28-41-11	D39914			FC	D11306			FA	ALL
1301ZO			EN		0-0	28-41-11	D39914		S/R		D11306		S/R		ALL
1302	20	C1	EP		57-8	28-41-11	D39914	21			D11306	23			YC051-YC055
1302	20	C1	EP		58-1	28-41-11	D39914	21			D11306	23			YC056-YL999, YR301-YR328
1302	20	C1	EP		47-5	28-41-11	D39914	21			D11306	23			YN231-YN501
1302Z			EP		0-0	28-41-11	D39914		S/R		D11306		S/R		ALL
1303	20	C1	EQ		57-8	28-41-11	D39914	20			D11306	22			YC051-YC055
1303	20	C1	EQ		58-1	28-41-11	D39914	20			D11306	22			YC056-YL999, YR301-YR328
1303	20	C1	EQ		47-5	28-41-11	D39914	20			D11306	22			YN231-YN501
1303Z			EQ		0-0	28-41-11	D39914		S/R		D11306		S/R		ALL
2601B	22	X2	SA		13-1	28-41-11	D11306	3			D48128P	A03			YC051-YD158
2601B	22	X2	SA		13-6	28-41-11	D11306	3			D48128P	A03			YD160-YR328
2601R	22	X2	SA		0-0	28-41-11	D11306	1			D48128P	A02			ALL
2601Z			SA		0-0	28-41-11	D11306		S/R		D48128P		PERG	1F	ALL
2602B	22	X2	SB		13-1	34-61-14	D11306	31			D48128P	A07			YC051-YD158
2602B	22	X2	SB		13-6	34-61-14	D11306	31			D48128P	A07			YD160-YR328
2602R	22	X2	SB		0-0	34-61-14	D11306	18			D48128P	A06			ALL
2602Z			SB		0-0	34-61-14	D11306		S/R		D48128P		PERG	1F	ALL
2607B	22	X2	SG		13-1	28-41-11	D11306	24			D48128P	A04			YC051-YD158
2607B	22	X2	SG		13-6	28-41-11	D11306	24			D48128P	A04			YD160-YR328
2607R	22	X2	SG		0-0	28-41-11	D11306	25			D48128P	A05			ALL
2607Z			SG		0-0	28-41-11	D11306		S/R		D48128P		PERG	1F	ALL
6001	22	PA			1-3	28-41-11	D11306	2			D11306	CAP	Y		ALL
6002	22	PA			1-3	28-41-11	D11306	7			D11306	CAP	Y		ALL
6003	22	PA			1-3	28-41-11	D11306	20			D11306	CAP	Y		ALL
6004	22	PA			1-3	28-41-11	D11306	21			D11306	CAP	Y		ALL
6005	22	PA			0-7	28-41-11	D11306	12			D11306				ALL
6007	22	PA			13-0	28-41-11	D48128P	A01			D11354	1			YC051-YD158
6007	22	PA			13-5	28-41-11	D48128P	A01			D11354	1			YD160-YR328
6008	20	PA			1-11	28-41-11	D11354	2			GD00020	DC..	E		ALL
6009	20	PA			1-4	28-41-11	D39914	38			D39914		S/R		ALL
6010	20	PA			1-4	28-41-11	D39914	39			D39914				ALL
6011	20	PA			1-4	28-41-11	D39914	6			D39914				ALL

WIRE LIST

D280A108

91-21-11

Section W6570

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6570		286A6570			RIGHT WING BODY PRESS SEAL TO RADAR BAY (continued)											
	FRAA					0-0	28-41-11	D11306		9		D11306			FA	ALL
	FRAB					0-0	28-41-11	D11306		19		D11306			FA	ALL
	FRAC					0-0	28-41-11	D39914		18		D39914			FC	ALL
	FRAD					0-0	28-41-11	D39914		37		D39914			FC	ALL

For training purposes only!

WIRE LIST

D280A108

91-21-11

Section W6570

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W6586	286A6586				RIGHT WING BODY PRESS SEAL TO E/E BAY											
0001	16		PA		35-4	33-45-11		D39906		17		D40164P		F		YC051-YC055
0001	16		PA		35-6	33-45-11		D39906		17		D40164P		F		YC056-YD153
0001	16		PA		35-6	33-45-11		D39906		10		D40164P		F		YD154-YL999, YR301-YR328
0001	16		PA		26-0	33-45-11		D39906		10		D40164P		F		YN231-YN501
0002	20		PA		35-4	33-44-12		D39906		19		D40164P		A01		YC051-YC055
0002	20		PA		35-6	33-44-12		D39906		19		D40164P		A01		YC056-YL999, YR301-YR328
0002	20		PA		26-0	33-44-12		D39906		19		D40164P		A01		YN231-YN501
0003	18		PA		35-4	33-42-11		D39906		16		D40164P		G		YC051-YC055
0003	18		PA		35-6	33-42-11		D39906		16		D40164P		G		YC056-YL999, YR301-YR328
0003	18		PA		26-0	33-42-11		D39906		16		D40164P		G		YN231-YN501
0004	20		PA		35-4	33-43-11		D39906		20		D40164P		B01		YC051-YC055
0004	20		PA		35-6	33-43-11		D39906		20		D40164P		B01		YC056-YL999, YR301-YR328
0004	20		PA		26-0	33-43-11		D39906		20		D40164P		B01		YN231-YN501
2601B	22	X2	SA		35-4	28-41-11		D39906		23		D40164P		A10		YC051-YC055
2601B	22	X2	SA		35-6	28-41-11		D39906		23		D40164P		A10		YC056-YL999, YR301-YR328
2601B	22	X2	SA		26-0	28-41-11		D39906		23		D40164P		A10		YN231-YN501
2601R	22	X2	SA		0-0	28-41-11		D39906		22		D40164P		B10		ALL
2601Z			SA		0-0	28-41-11		D39906	S/R			D40164P	PERG	1F		ALL
2602B	20	PB	SB		6-10	28-44-11		D39906		31		TB0205W	B009	1		YC051-YL999, YR301-YR328
2602B	20	PB	SB		7-1	28-44-11		D39906		31		TB0205W	B009	1		YN231-YN501
2602R	20	PB	SB		0-0	28-44-11		D39906		29		TB0205V	B015	1		ALL
3801B	20	X3	A8		6-9	23-41-11		D39906		26		TB0205W	B001	1		YC051-YL999, YR301-YR328
3801B	20	X3	A8		7-0	23-41-11		D39906		26		TB0205W	B001	1		YN231-YN501
3801R	20	X3	A8		0-0	23-41-11		D39906		25		TB0205W	A001	1		ALL
3801Y	20	X3	A8		0-0	23-41-11		D39906		27		TB0205W	A005	1		ALL
3801Z			A8		0-0	23-41-11		D39906		11		TB0205W	B005	1		ALL
6001	22	PA			35-4	30-11-11		D39906		8		D40164P	A02			YC051-YC055
6001	22	PA			35-6	30-11-11		D39906		8		D40164P	A02			YC056-YL999, YR301-YR328
6001	22	PA			26-0	30-11-11		D39906		8		D40164P	A02			YN231-YN501
6002	22	PA			35-4	30-11-11		D39906		5		D40164P	B02			YC051-YC055

WIRE LIST

D280A108

91-21-11
Section W6580
Page 1
Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W6586	286A6586				RIGHT WING BODY PRESS SEAL TO E/E BAY (continued)											
6002	22		PA		35-6	30-11-11		D39906			5		D40164P	B02		YC056-YL999, YR301-YR328
6002	22		PA		26-0	30-11-11		D39906			5		D40164P	B02		YN231-YN501
6003	18		PA		35-4	28-44-11		D39906			12		D40164P	H		YC051-YC055
6003	18		PA		35-6	28-44-11		D39906			12		D40164P	H		YC056-YL999, YR301-YR328
6003	18		PA		26-0	28-44-11		D39906			12		D40164P	H		YN231-YN501
6004	22		PA		35-4	28-44-11		D39906			28		D40164P	B08		YC051-YC055
6004	22		PA		35-6	28-44-11		D39906			28		D40164P	B08		YC056-YL999, YR301-YR328
6004	22		PA		26-0	28-44-11		D39906			28		D40164P	B08		YN231-YN501
6005	20		PA		35-6	28-44-11		D39906			32		D40164P	B05		YD160-YL999, YR301-YR328
6005	20		PA		26-0	28-44-11		D39906			32		D40164P	B05		YN231-YN501
6009	22		PA		35-4	28-43-11		D39906			30		D40164P	A09		YC051-YC055
6009	22		PA		35-6	28-43-11		D39906			30		D40164P	A09		YC056-YL999, YR301-YR328
6009	22		PA		26-0	28-43-11		D39906			30		D40164P	A09		YN231-YN501
6010	20		PA		35-4	28-44-11		D39906			33		D40164P	B09		YC051-YC055
6010	20		PA		35-6	28-44-11		D39906			33		D40164P	B09		YC056-YL999, YR301-YR328
6010	20		PA		26-0	28-44-11		D39906			33		D40164P	B09		YN231-YN501
W6588	286A6588				RIGHT WING BODY PRESS SEAL TO E/E BAY											
0007	20		PA		27-11	21-31-23		D40714P			B06		D40160P	A09		YD158-YR328
0008	24		PK		27-11	21-31-23		D40160P			A10		D40714P	B07		YD158-YR328
1303	22		X1	EQ	30-1	28-43-11		D41850J			1		D40714P	A01		YC051-YC055
1303	22		X1	EQ	30-3	28-43-11		D41850J			1		D40714P	A01		YC056-YL999, YR301-YR328
1303	22		X1	EQ	20-6	28-43-11		D41850J			1		D40714P	A01		YN231-YN501
1303Z				EQ	0-0	28-43-11		D41850J			DED		D40714P	DED		ALL
1304	22		X1	ER	30-0	28-43-11		D41856J			1		D40714P	B01		YC051-YC055
1304	22		X1	ER	30-2	28-43-11		D41856J			1		D40714P	B01		YC056-YL999, YR301-YR328
1304	22		X1	ER	20-4	28-43-11		D41856J			1		D40714P	B01		YN231-YN501
1304Z				ER	0-0	28-43-11		D41856J			DED		D40714P	PERG	1F	ALL
1305	20		X1	ES	30-1	28-22-11		D40714P			A06		D41850J	5		YC051-YC055
1305	20		X1	ES	30-3	28-22-11		D40714P			A06		D41850J	5		YC056-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W6580

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6588	286A6588				RIGHT WING BODY PRESS SEAL TO E/E BAY (continued)										
1305	20	X1	ES		20-6	28-22-11	D40714P	A06			D41850J	5			YN231-YN501
1305Z			ES		0-0	28-22-11	D40714P	PERG	1F		D41850J	DED			ALL
1306	20	X1	ET		30-1	28-22-11	D40714P	A07			D41850J	6			YC051-YC055
1306	20	X1	ET		30-3	28-22-11	D40714P	A07			D41850J	6			YC056-YL999, YR301-YR328
1306	20	X1	ET		20-6	28-22-11	D40714P	A07			D41850J	6			YN231-YN501
1306Z			ET		0-0	28-22-11	D40714P	PERG	1F		D41850J	DED			ALL
1309	20	X1	EW		30-1	28-22-11	D40714P	A08			D41850J	7			YC051-YC055
1309	20	X1	EW		30-3	28-22-11	D40714P	A08			D41850J	7			YC056-YL999, YR301-YR328
1309	20	X1	EW		20-6	28-22-11	D40714P	A08			D41850J	7			YN231-YN501
1309Z			EW		0-0	28-22-11	D40714P	PERG	1F		D41850J	DED			ALL
2201B	20	PB	KA		53-4	27-81-21	D39939	29			D40160P	A01			YC051-YC055
2201B	20	PB	KA		53-5	27-81-21	D39939	29			D40160P	A01			YC056-YD157
2201B	20	PB	KA		53-6	27-81-21	D39939	29			D40160P	A01			YD158-YL999, YR301-YR328
2201B	20	PB	KA		43-4	27-81-21	D39939	29			D40160P	A01			YN231-YN501
2201R	20	PB	KA		0-0	27-81-21	D39939	13			D40160P	B01			ALL
2202B	20	PB	KB		53-4	27-81-21	D39939	30			D40160P	A02			YC051-YC055
2202B	20	PB	KB		53-5	27-81-21	D39939	30			D40160P	A02			YC056-YD157
2202B	20	PB	KB		53-6	27-81-21	D39939	30			D40160P	A02			YD158-YL999, YR301-YR328
2202B	20	PB	KB		43-4	27-81-21	D39939	30			D40160P	A02			YN231-YN501
2202R	20	PB	KB		0-0	27-81-21	D39939	31			D40160P	B02			ALL
2203B	20	PB	KC		53-4	27-81-21	D39939	32			D40160P	A03			YC051-YC055
2203B	20	PB	KC		53-5	27-81-21	D39939	32			D40160P	A03			YC056-YD157
2203B	20	PB	KC		53-6	27-81-21	D39939	32			D40160P	A03			YD158-YL999, YR301-YR328
2203B	20	PB	KC		43-4	27-81-21	D39939	32			D40160P	A03			YN231-YN501
2203R	20	PB	KC		0-0	27-81-21	D39939	33			D40160P	B03			ALL
2204B	20	PB	KD		53-4	27-81-21	D39939	35			D40160P	A04			YC051-YC055
2204B	20	PB	KD		53-5	27-81-21	D39939	35			D40160P	A04			YC056-YD157
2204B	20	PB	KD		53-6	27-81-21	D39939	35			D40160P	A04			YD158-YL999, YR301-YR328
2204B	20	PB	KD		43-4	27-81-21	D39939	35			D40160P	A04			YN231-YN501
2204R	20	PB	KD		0-0	27-81-21	D39939	34			D40160P	B04			ALL
3601B	20	PC	A4		29-11	28-23-11	D05342J	2			D40714P	A05			YC051-YC055
3601B	20	PC	A4		30-1	28-23-11	D05342J	2			D40714P	A05			YC056-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W6580

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6588		286A6588			RIGHT WING BODY PRESS SEAL TO E/E BAY (continued)											
3601B		20		PC	A4	20-4	28-23-11	D05342J		2		D40714P		A05		YN231-YN501
3601R		20		PC	A4	0-0	28-23-11	D05342J		4		D40714P		A03		ALL
3601Y		20		PC	A4	0-0	28-23-11	D05342J		3		D40714P		A04		ALL
3602B		18		PC	B4	30-1	28-23-11	D05350J		13		D40714P		J		YC051-YC055
3602B		18		PC	B4	30-3	28-23-11	D05350J		13		D40714P		J		YC056-YL999, YR301-YR328
3602B		18		PC	B4	20-5	28-23-11	D05350J		13		D40714P		J		YN231-YN501
3602R		18		PC	B4	0-0	28-23-11	D05350J		11		D40714P		G		ALL
3602Y		18		PC	B4	0-0	28-23-11	D05350J		12		D40714P		H		ALL
3603B		20		PC	C4	35-3	28-23-11	D39939		1		D40714P		B05		YC051-YC055
3603B		20		PC	C4	35-4	28-23-11	D39939		1		D40714P		B05		YC056-YD157
3603B		20		PC	C4	35-5	28-23-11	D39939		1		D40714P		B05		YD158-YL999, YR301-YR328
3603B		20		PC	C4	25-9	28-23-11	D39939		1		D40714P		B05		YN231-YN501
3603R		20		PC	C4	0-0	28-23-11	D39939		3		D40714P		B03		YC051-YD153
3603R		20		PC	C4	0-0	28-23-11	D39939		9		D40714P		B03		YD154-YR328
3603Y		20		PC	C4	0-0	28-23-11	D39939		5		D40714P		B04		YC051-YD153
3603Y		20		PC	C4	0-0	28-23-11	D39939		17		D40714P		B04		YD154-YR328

WIRE LIST

D280A108

91-21-11

Section W6580

Page 4 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W6730	286A6730				DISC AL0720D TO E1-3, E2-2											
0513	20		PA		60-10	49-62-11		D43050P		B03		D46050J	1			YC051-YC055
0513	20		PA		61-0	49-62-11		D43050P		B03		D46050J	1			YC056-YD158
0513	20		PA		60-11	49-62-11		D43050P		B03		D46050J	1			YD160-YL999, YR301-YR328
0513	20		PA		50-4	49-62-11		D43050P		B03		D46050J	1			YN231-YN501
0514	20		PA		60-10	49-62-11		D43050P		A04		D46050J	2			YC051-YC055
0514	20		PA		61-0	49-62-11		D43050P		A04		D46050J	2			YC056-YD158
0514	20		PA		60-11	49-62-11		D43050P		A04		D46050J	2			YD160-YL999, YR301-YR328
0514	20		PA		50-4	49-62-11		D43050P		A04		D46050J	2			YN231-YN501
0515	22		PA		22-9	32-41-11		D43050P		B04		D43048P	6			YC051-YC055
0515	22		PA		22-11	32-41-11		D43050P		B04		D43048P	6			YC056-YR328
0591	22		PA		69-10	32-41-11		D43048P		5		D46050J	9			YC051-YC055
0591	22		PA		69-7	32-41-11		D43048P		5		D46050J	9			YC056-YD158
0591	22		PA		69-5	32-41-11		D43048P		5		D46050J	9			YD160-YL999, YR301-YR328
0591	22		PA		59-4	32-41-11		D43048P		5		D46050J	9			YN231-YN501
0592	22		PA		20-9	32-41-11		GD05101	DC..	1		D46050J	10			YC051-YD158
0592	22		PA		20-8	32-41-11		GD05101	DC..	1		D46050J	10			YD160-YL999, YR301-YR328
0592	22		PA		20-4	32-41-11		GD05101	DC..	1		D46050J	10			YN231-YN501
2001B	20		Y6	GA	69-10	29-32-11		D43048P		4		D46050J	4			YC051-YC055
2001B	20		Y6	GA	69-7	29-32-11		D43048P		4		D46050J	4			YC056-YD158
2001B	20		Y6	GA	69-5	29-32-11		D43048P		4		D46050J	4			YD160-YL999, YR301-YR328
2001B	20		Y6	GA	59-4	29-32-11		D43048P		4		D46050J	4			YN231-YN501
2001R	20		Y6	GA	0-0	29-32-11		D43048P		3		D46050J	3			ALL
2001Z				GA	0-0	29-32-11		D43048P		2		D46050J	S/R			ALL
2201B	22		VG	KA	60-10	24-22-31		D43050P		A07		D46050J	15			YC051-YC055
2201B	22		VG	KA	61-0	24-22-31		D43050P		A07		D46050J	15			YC056-YD158
2201B	22		VG	KA	60-11	24-22-31		D43050P		A07		D46050J	15			YD160-YL999, YR301-YR328
2201B	22		VG	KA	50-4	24-22-31		D43050P		A07		D46050J	15			YN231-YN501
2201R	22		VG	KA	0-0	24-22-31		D43050P		B07		D46050J	16			ALL
2201Z				KA	0-0	24-22-31		D43050P		DED		D46050J	DED			ALL
6001R	20		9P		60-10	26-11-31		D43050P		A01		D46050J	11			YC051-YC055
6001R	20		9P		61-0	26-11-31		D43050P		A01		D46050J	11			YC056-YD158
6001R	20		9P		60-11	26-11-31		D43050P		A01		D46050J	11			YD160-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11

Section W6730

Page 1

Nov 12/2012

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To					
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W6730	286A6730				DISC AL0720D TO E1-3, E2-2 (continued)											
6001R	20		9P		50-4	26-11-31		D43050P	A01			D46050J	11			YN231-YN501
6002R	20		9P		60-10	26-11-31		D43050P	B01			D46050J	12			YC051-YC055
6002R	20		9P		61-0	26-11-31		D43050P	B01			D46050J	12			YC056-YD158
6002R	20		9P		60-11	26-11-31		D43050P	B01			D46050J	12			YD160-YL999, YR301-YR328
6002R	20		9P		50-4	26-11-31		D43050P	B01			D46050J	12			YN231-YN501
6003R	20		9P		60-10	26-11-31		D43050P	A02			D46050J	13			YC051-YC055
6003R	20		9P		61-0	26-11-31		D43050P	A02			D46050J	13			YC056-YD158
6003R	20		9P		60-11	26-11-31		D43050P	A02			D46050J	13			YD160-YL999, YR301-YR328
6003R	20		9P		50-4	26-11-31		D43050P	A02			D46050J	13			YN231-YN501
6004R	20		9P		60-10	26-11-31		D43050P	B02			D46050J	18			YC051-YC055
6004R	20		9P		61-0	26-11-31		D43050P	B02			D46050J	18			YC056-YD158
6004R	20		9P		60-11	26-11-31		D43050P	B02			D46050J	18			YD160-YL999, YR301-YR328
6004R	20		9P		50-4	26-11-31		D43050P	B02			D46050J	18			YN231-YN501
6005R	20		9P		60-10	26-11-31		D43050P	A03			D46050J	19			YC051-YC055
6005R	20		9P		61-0	26-11-31		D43050P	A03			D46050J	19			YC056-YD158
6005R	20		9P		60-11	26-11-31		D43050P	A03			D46050J	19			YD160-YL999, YR301-YR328
6005R	20		9P		50-4	26-11-31		D43050P	A03			D46050J	19			YN231-YN501
6006R	20		9P		69-10	26-21-11		D43048P	7			D46050J	7			YC051-YC055
6006R	20		9P		69-7	26-21-11		D43048P	7			D46050J	7			YC056-YD158
6006R	20		9P		69-5	26-21-11		D43048P	7			D46050J	7			YD160-YL999, YR301-YR328
6006R	20		9P		59-4	26-21-11		D43048P	7			D46050J	7			YN231-YN501
6007R	20		9P		69-10	26-21-11		D43048P	8			D46050J	8			YC051-YC055
6007R	20		9P		69-7	26-21-11		D43048P	8			D46050J	8			YC056-YD158
6007R	20		9P		69-5	26-21-11		D43048P	8			D46050J	8			YD160-YL999, YR301-YR328
6007R	20		9P		59-4	26-21-11		D43048P	8			D46050J	8			YN231-YN501
W6732	286A6732				DISC AL0675C TO E1-3, E3-2											
0001	20		PA		55-4	27-62-11		D43054P	B12			D46046J	33			YL953-YL999, YR301-YR328
0002	20		PA		55-4	27-62-11		D43054P	B13			D46046J	32			YL953-YL999, YR301-YR328
0501	22		PA		56-5	27-62-21		D43054P	B10			D46046J	6			YC051-YC068

WIRE LIST

D280A108

91-21-11

Section W6730

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6732	286A6732			DISC AL0675C TO E1-3, E3-2 (continued)											
0501	22		PA		55-4	27-62-21	D43054P	B10			D46046J	6			YC070-YL999, YR301-YR328
0501	22		PA		44-9	27-62-21	D43054P	B10			D46046J	6			YN231-YN501
0503	22		PA		56-5	31-53-11	D43054P	A11			D46046J	5			YC051-YC068
0503	22		PA		55-4	31-53-11	D43054P	A11			D46046J	5			YC070-YL999, YR301-YR328
0503	22		PA		44-9	31-53-11	D43054P	A11			D46046J	5			YN231-YN501
0591	22		PA		56-5	32-41-11	D43054P	B02			D46046J	7			YC051-YC068
0591	22		PA		55-4	32-41-11	D43054P	B02			D46046J	7			YC070-YL999, YR301-YR328
0591	22		PA		44-9	32-41-11	D43054P	B02			D46046J	7			YN231-YN501
0592	22		PA		16-8	32-41-11	GD05101	DC..	1		D46046J	8			YC051-YC068
0592	22		PA		15-7	32-41-11	GD05101	DC..	1		D46046J	8			YC070-YL999, YR301-YR328
0592	22		PA		15-3	32-41-11	GD05101	DC..	1		D46046J	8			YN231-YN501
2211B	22		X2	KK	56-5	32-41-11	D43054P	B01			D46046J	29			YC051-YC068
2211B	22		X2	KK	55-4	32-41-11	D43054P	B01			D46046J	29			YC070-YL999, YR301-YR328
2211B	22		X2	KK	44-9	32-41-11	D43054P	B01			D46046J	29			YN231-YN501
2211R	22		X2	KK	0-0	32-41-11	D43054P	A01			D46046J	28			ALL
2211Z				KK	0-0	32-41-11	D43054P	A02			D46046J	30	18		ALL
2213B	22		PB	KM	56-5	32-64-11	D43054P	A08			D46046J	12			YC051-YC068
2213B	22		PB	KM	55-4	32-64-11	D43054P	A08			D46046J	12			YC070-YL999, YR301-YR328
2213B	22		PB	KM	44-9	32-64-11	D43054P	A08			D46046J	12			YN231-YN501
2213R	22		PB	KM	0-0	32-64-11	D43054P	B07			D46046J	11			ALL
2214B	22		PB	KN	56-5	32-64-11	D43054P	A09			D46046J	2			YC051-YC068
2214B	22		PB	KN	55-4	32-64-11	D43054P	A09			D46046J	2			YC070-YL999, YR301-YR328
2214B	22		PB	KN	44-9	32-64-11	D43054P	A09			D46046J	2			YN231-YN501
2214R	22		PB	KN	0-0	32-64-11	D43054P	B08			D46046J	1			ALL
2240B	22		PB	LP	56-5	32-31-11	D43054P	A10			D46046J	15			YC051-YC068
2240B	22		PB	LP	55-4	32-31-11	D43054P	A10			D46046J	15			YC070-YL999, YR301-YR328
2240B	22		PB	LP	44-9	32-31-11	D43054P	A10			D46046J	15			YN231-YN501
2240R	22		PB	LP	0-0	32-31-11	D43054P	B09			D46046J	14			ALL
2601B	20		PB	SA	56-5	78-36-21	D46046J		24		D43054P	B05			YC051-YC068
2601B	20		PB	SA	55-4	78-36-21	D46046J		24		D43054P	B05			YC070-YL999, YR301-YR328

WIRE LIST

D280A108

91-21-11
Section W6730
Page 3
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W6732		286A6732			DISC AL0675C TO E1-3, E3-2 (continued)											
2601B		20		PB	SA	44-9	78-36-21	D46046J	24			D43054P	B05			YN231-YN501
2601R		20		PB	SA	0-0	78-36-21	D46046J	22			D43054P	A06			ALL
2602B		20		PB	SB	56-5	78-36-21	D46046J	27			D43054P	B06			YC051-YC068
2602B		20		PB	SB	55-4	78-36-21	D46046J	27			D43054P	B06			YC070-YL999, YR301-YR328
2602B		20		PB	SB	44-9	78-36-21	D46046J	27			D43054P	B06			YN231-YN501
2602R		20		PB	SB	0-0	78-36-21	D46046J	25			D43054P	A07			ALL
6001		20		CQ		56-5	78-34-21	D46046J	21			D43054P	A03			YC051-YC068
6001		20		CQ		55-4	78-34-21	D46046J	21			D43054P	A03			YC070-YL999, YR301-YR328
6001		20		CQ		44-9	78-34-21	D46046J	21			D43054P	A03			YN231-YN501
6002		20		CQ		56-5	78-34-21	D46046J	18			D43054P	B03			YC051-YC068
6002		20		CQ		55-4	78-34-21	D46046J	18			D43054P	B03			YC070-YL999, YR301-YR328
6002		20		CQ		44-9	78-34-21	D46046J	18			D43054P	B03			YN231-YN501
6003		20		CQ		56-5	78-34-21	D46046J	19			D43054P	A04			YC051-YC068
6003		20		CQ		55-4	78-34-21	D46046J	19			D43054P	A04			YC070-YL999, YR301-YR328
6003		20		CQ		44-9	78-34-21	D46046J	19			D43054P	A04			YN231-YN501
6004		20		CQ		56-5	78-34-21	D46046J	16			D43054P	B04			YC051-YC068
6004		20		CQ		55-4	78-34-21	D46046J	16			D43054P	B04			YC070-YL999, YR301-YR328
6004		20		CQ		44-9	78-34-21	D46046J	16			D43054P	B04			YN231-YN501
6005		20		CQ		56-5	78-34-21	D46046J	17			D43054P	A05			YC051-YC068
6005		20		CQ		55-4	78-34-21	D46046J	17			D43054P	A05			YC070-YL999, YR301-YR328
6005		20		CQ		44-9	78-34-21	D46046J	17			D43054P	A05			YN231-YN501
6006		20		CQ		16-8	78-34-21	D46046J	20			GD05101	DC..	1		YC051-YC068
6006		20		CQ		15-7	78-34-21	D46046J	20			GD05101	DC..	1		YC070-YL999, YR301-YR328
6006		20		CQ		15-3	78-34-21	D46046J	20			GD05101	DC..	1		YN231-YN501
6007		20		PA		16-8	78-36-21	D46046J	23			GD05101	DC..	1		YC051-YC068
6007		20		PA		15-7	78-36-21	D46046J	23			GD05101	DC..	1		YC070-YL999, YR301-YR328
6007		20		PA		15-3	78-36-21	D46046J	23			GD05101	DC..	1		YN231-YN501
6008		20		PA		16-8	78-36-21	D46046J	26			GD05101	DC..	1		YC051-YC068
6008		20		PA		15-7	78-36-21	D46046J	26			GD05101	DC..	1		YC070-YL999, YR301-YR328
6008		20		PA		15-3	78-36-21	D46046J	26			GD05101	DC..	1		YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W6730

Page 4 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W7022	286A7022				#1 LEFT GEAR DOWN AND LOCKED SENSOR											
A-B					0-0	32-64-11		D46002P		2		S00071	BLU			ALL
A-R					0-0	32-64-11		D46002P		1		S00071	RED			ALL
A-Y					0-0	32-64-11		D46002P		3		S00071	YEL			ALL
W7024	286A7024				#2 LEFT GEAR DOWN AND LOCKED SENSOR											
A-B					0-0	32-64-12		D46008P		2		S00302	BLU			ALL
A-R					0-0	32-64-12		D46008P		1		S00302	RED			ALL
A-Y					0-0	32-64-12		D46008P		3		S00302	YEL			ALL
W7026	286A7026				FWD LEFT SIDE, WHEEL WELL AREA											
0501	18		HA		7-1	49-62-11		D46026P		1		D00920		1		YC051-YC055
0501	18		HA		7-3	49-62-11		D46026P		1		D00920		1		YC056-YD152
0501	18		HA		7-7	49-62-11		D46026P		1		D00920		1		YD153-YD157
0501	18		HA		7-8	49-62-11		D46026P		1		D00920		1		YD158-YR323, YR325-YR328
0502	18		HA		7-1	49-62-11		D46026P		2		D00920		2		YC051-YC055
0502	18		HA		7-3	49-62-11		D46026P		2		D00920		2		YC056-YD152
0502	18		HA		7-7	49-62-11		D46026P		2		D00920		2		YD153-YD157
0502	18		HA		7-8	49-62-11		D46026P		2		D00920		2		YD158-YR323, YR325-YR328
0503	18		HA		7-1	49-62-11		D46026P		3		D00920		3		YC051-YC055
0503	18		HA		7-3	49-62-11		D46026P		3		D00920		3		YC056-YD152
0503	18		HA		7-7	49-62-11		D46026P		3		D00920		3		YD153-YD157
0503	18		HA		7-8	49-62-11		D46026P		3		D00920		3		YD158-YR323, YR325-YR328
0504	18		HA		7-1	49-62-11		D46026P		4		D00920		4		YC051-YC055
0504	18		HA		7-3	49-62-11		D46026P		4		D00920		4		YC056-YD152
0504	18		HA		7-7	49-62-11		D46026P		4		D00920		4		YD153-YD157
0504	18		HA		7-8	49-62-11		D46026P		4		D00920		4		YD158-YR323, YR325-YR328
0505	18		HA		3-5	49-62-11		GD00330	DC..	E		D00920		5		YC051-YC055
0505	18		HA		3-7	49-62-11		GD00330	DC..	E		D00920		5		YC056-YD152
0505	18		HA		2-6	49-62-11		GD00330	DC..	E		D00920		5		YD153-YR323, YR325-YR328
0506	18		HA		11-11	33-32-11		D46026P		9		S00064		1	C	YC051-YC055
0506	18		HA		12-0	33-32-11		D46026P		9		S00064		1	C	YC056-YD152
0506	18		HA		13-5	33-32-11		D46026P		9		S00064		1	C	YD153-YL963, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W7020

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7026	286A7026			FWD LEFT SIDE, WHEEL WELL AREA (continued)											
0506	18		HA		13-6	33-32-11	D46026P		9		S00064	1	C		YL964-YL999, YN236-YR323, YR325-YR328
0507	18		HA		11-11	33-32-11	D46026P		5		S00064	3	C		YC051-YC055
0507	18		HA		12-0	33-32-11	D46026P		5		S00064	3	C		YC056-YD152
0507	18		HA		13-5	33-32-11	D46026P		5		S00064	3	C		YD153-YR323, YR325-YR328
0508	18		HA		10-0	33-32-11	SM00001		9		S00064	2	C		YC051-YC055
0508	18		HA		10-7	33-32-11	SM00001		9		S00064	2	C		YC056-YD152
0508	18		HA		11-11	33-32-11	SM00001		9		S00064	2	C		YD153-YL963, YN231-YN235
0508	18		HA		12-0	33-32-11	SM00001		9		S00064	2	C		YL964-YL999, YN236-YR323, YR325-YR328
0509	18		HA		26-8	33-32-11	SM00001		9		L00172	=P	I		YC051-YC055
0509	18		HA		26-4	33-32-11	SM00001		9		L00172	=P	I		YC056-YD152
0509	18		HA		13-6	33-32-11	SM00001		9		L00172	=P	I		YD153-YR323, YR325-YR328
0510	18		HA		20-6	33-32-11	SM00001		9		L00173	=P	I	*	YC051-YC055
0510	18		HA		19-11	33-32-11	SM00001		9		L00173	=P	I	*	YC056-YD152
0510	18		HA		20-10	33-32-11	SM00001		9		L00173	=P	I	*	YD153-YL963, YN231-YN235
0510	18		HA		23-0	33-32-11	SM00001		9		L00173	=P	I	*	YL964-YL999, YN236-YR323, YR325-YR328
0511	18		HA		7-9	33-32-11	SM00001		9		L00174	=P	BK		YC051-YC055
0511	18		HA		7-10	33-32-11	SM00001		9		L00174	=P	BK		YC056-YD152
0511	18		HA		7-4	33-32-11	SM00001		9		L00174	=P	BK		YD153-YL963, YN231-YN235
0511	18		HA		7-5	33-32-11	SM00001		9		L00174	=P	BK		YL964-YL999, YN236-YR323, YR325-YR328
0512	18		HA		11-1	33-32-11	L00173	=P	I	*	L00175	=P	BK		YC051-YD152
0512	18		HA		12-6	33-32-11	L00173	=P	I	*	L00175	=P	BK		YD153-YL963, YN231-YN235
0512	18		HA		14-8	33-32-11	L00173	=P	I	*	L00175	=P	BK		YL964-YL999, YN236-YR323, YR325-YR328
0513	18		HA		1-9	33-32-11	GD00090	AC..	E		L00172	=G	E		YC051-YC058

WIRE LIST

D280A108

91-21-11

Section W7020

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7026	286A7026			FWD LEFT SIDE, WHEEL WELL AREA (continued)											
0513	18		HA		1-7	33-32-11	GD00090	AC..	E		L00172	=G	E		YC059-YD152
0513	18		HA		2-3	33-32-11	GD00090	AC..	E		L00172	=G	E		YD153-YR323, YR325-YR328
0514	18		HA		1-7	33-32-11	GD00092	AC..	E		L00173	=G	E		YC051-YC055, YD153-YR323, YR325-YR328
0514	18		HA		1-5	33-32-11	GD00092	AC..	E		L00173	=G	E		YC056-YD152
0515	18		HA		6-11	33-32-11	GD01948	AC..	E		L00174	=G	C		YC051-YC058
0515	18		HA		7-8	33-32-11	GD01948	AC..	E		L00174	=G	C		YC059-YD152
0515	18		HA		4-3	33-32-11	GD01948	AC..	E		L00174	=G	C		YD153-YR323, YR325-YR328
0516	18		HA		10-2	33-32-11	GD01950	AC..	E		L00175	=G	C		YC051-YC055
0516	18		HA		10-5	33-32-11	GD01950	AC..	E		L00175	=G	C		YC056-YC058
0516	18		HA		10-10	33-32-11	GD01950	AC..	E		L00175	=G	C		YC059-YL955, YN231-YN235
0516	18		HA		10-6	33-32-11	GD01950	AC..	E		L00175	=G	C		YL956-YL963
0516	18		HA		10-1	33-32-11	GD01950	AC..	E		L00175	=G	C		YL964-YL999, YN236-YR323, YR325-YR328
0517	20		HA		4-8	32-35-11	D46026P		6		D11734		1		YC051-YD152
0517	20		HA		6-2	32-35-11	D46026P		6		D11734		1		YD153-YD157
0517	20		HA		6-3	32-35-11	D46026P		6		D11734		1		YD158-YR323, YR325-YR328
0518	20		HA		4-8	32-35-11	D46026P		8		D11734		2		YC051-YD152
0518	20		HA		6-2	32-35-11	D46026P		8		D11734		2		YD153-YD157
0518	20		HA		6-3	32-35-11	D46026P		8		D11734		2		YD158-YR323, YR325-YR328
0519	20		HA		3-0	32-35-11	GD00947	ST..	E		D11734		3		YC051-YC055
0519	20		HA		3-1	32-35-11	GD00947	ST..	E		D11734		3		YC056-YD152
0519	20		HA		3-8	32-35-11	GD00947	ST..	E		D11734		3		YD153-YR323, YR325-YR328
2201B	18		HF	KA	7-10	32-41-11	D46026P		11		D02874		2		YC051-YD152
2201B	18		HF	KA	8-8	32-41-11	D46026P		11		D02874		2		YD153-YR323, YR325-YR328
2201R	18		HF	KA	0-0	32-41-11	D46026P		10		D02874		1		YC051-YR323, YR325-YR328
2201Z				KA	0-0	32-41-11	D46026P		S/R		D02874		S/R		YC051-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W7020

Page 3 End

Nov 12/2012

Bundle No.	Part Number			Description	From			To			Effectivity				
	Wire No.	GA	CO TY		Fam	FT-IN	Diagram	Equip	Term	Type		Splice	Equip	Term	Type
W7030	286A7030			AB1030C DISC (STA 1038) TO LEFT ELEVATOR DISC											
0522	18		HL		18-3	27-31-11	D10531		1		D40236P		1		YC056-YR328
0523	18		HL		13-2	27-31-11	D10531		2		GD00060	DC..	1		YC056-YD153
0523	18		HL		13-2	27-31-11	D10531		2		GD00036	DC..	1		YD154-YL952, YN231-YN234 YL953-YL999, YN235-YR328
0523	18		HL		13-3	27-31-11	D10531		2		GD00036	DC..	1		
W7032	286A7032			#1 NOSE GEAR ON GROUND SENSOR											
A-B					0-0	32-31-11	TB0040K		C002	1		S01014	BLU		ALL
A-R					0-0	32-31-11	TB0040K		A002	1		S01014	RED		ALL
A-Y					0-0	32-31-11	TB0040K		E002	1		S01014	YEL		ALL
W7034	286A7034			#1 NOSE GEAR LOCKED SENSOR											
A-B					0-0	32-64-11	TB0040K		C001	1		S00846	BLU		ALL
A-R					0-0	32-64-11	TB0040K		A001	1		S00846	RED		ALL
A-Y					0-0	32-64-11	TB0040K		E001	1		S00846	YEL		ALL
W7036	286A7036			#1 NOSE GEAR DOWN SENSOR											
A-B					0-0	32-64-11	TB0042K		C001	1		S00845	BLU		ALL
A-R					0-0	32-64-11	TB0042K		A001	1		S00845	RED		ALL
A-Y					0-0	32-64-11	TB0042K		E001	1		S00845	YEL		ALL
W7038	286A7038			L ELEV DISC TO L ELEVPOS XMTR AND LOGO LIGHT											
0501	20		HL		18-11	33-49-11	D11110		2		D40188J		10		ALL
0502	20		HL		18-11	33-49-11	D11110		4		D40188J		7		ALL
0503	20		HL		18-11	33-49-11	D11110		5		D40188J		4		ALL
2201B	20		HM	KA	3-2	27-38-11	D03578		1		D40188J		1		YC051-YC060
2201B	20		HM	KA	2-8	27-38-11	D03578		1		D40188J		1		YC061-YR328
2201R	20		HM	KA	0-0	27-38-11	D03578		2		D40188J		2		ALL
3201B	20		HN	YA	3-2	27-38-11	D03578		5		D40188J		5		YC051-YC060
3201B	20		HN	YA	2-8	27-38-11	D03578		5		D40188J		5		YC061-YR328
3201R	20		HN	YA	0-0	27-38-11	D03578		4		D40188J		6		ALL
3201Y	20		HN	YA	0-0	27-38-11	D03578		3		D40188J		3		ALL

WIRE LIST

D280A108

91-21-11

Section W7030

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity	
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type
W7057	286A7057				HF-1 COUPLER										
0004	18		PA		2-3	23-11-11		D00341	D	18		GD00887	AC..	E	YC051-YC059
0004	18		PA		1-7	23-11-11		D00341	D	18		GD00887	AC..	E	YC060-YL955, YN231-YN235
0004	18		PA		1-8	23-11-11		D00341	D	18		GD00887	AC..	E	YL956-YL999, YN236-YR328
0005	20		PA		8-1	23-11-11		D00341	F			D04227P	5		YC051-YD170
0005	20		PA		7-11	23-11-11		D00341	F			D04227P	5		YL951-YL955, YN231-YN235
0005	20		PA		8-0	23-11-11		D00341	F			D04227P	5		YL956-YL999, YN236-YR328
0006	18		PA		2-3	23-11-11		D00341	G	18		GD00889	DC..	E	YC051-YC059
0006	18		PA		1-8	23-11-11		D00341	G	18		GD00889	DC..	E	YC060-YD170
0006	18		PA		1-7	23-11-11		D00341	G	18		GD00889	DC..	E	YL951-YL955, YN231-YN235
0006	18		PA		1-9	23-11-11		D00341	G	18		GD00889	DC..	E	YL956-YL999, YN236-YR328
0007	20		PA		8-1	23-11-11		D00341	H			D04227P	7		YC051-YD170
0007	20		PA		7-11	23-11-11		D00341	H			D04227P	7		YL951-YL955, YN231-YN235
0007	20		PA		8-0	23-11-11		D00341	H			D04227P	7		YL956-YL999, YN236-YR328
0008	22		PA		8-1	23-11-11		D00341	K			D04227P	8		YC051-YD170
0008	22		PA		7-11	23-11-11		D00341	K			D04227P	8		YL951-YL955, YN231-YN235
0008	22		PA		8-0	23-11-11		D00341	K			D04227P	8		YL956-YL999, YN236-YR328
0011	20		PA		8-1	23-11-11		D00341	S			D04227P	11		YC051-YD170
0011	20		PA		7-11	23-11-11		D00341	S			D04227P	11		YL951-YL955, YN231-YN235
0011	20		PA		8-0	23-11-11		D00341	S			D04227P	11		YL956-YL999, YN236-YR328
0012	20		PA		8-1	23-11-11		D04227P	12			D00341	C-		YC051-YD170
0012	20		PA		7-11	23-11-11		D04227P	12			D00341	C-		YL951-YL955, YN231-YN235
0012	20		PA		8-0	23-11-11		D04227P	12			D00341	C-		YL956-YL999, YN236-YR328
0013	20		PA		8-1	23-11-11		D04227P	13			D00341	B		YC051-YD170
0013	20		PA		7-11	23-11-11		D04227P	13			D00341	B		YL951-YL955, YN231-YN235

WIRE LIST
D280A108

91-21-11
Section W7050
Page 1
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7057	286A7057			HF-1 COUPLER (continued)											
0013	20		PA		8-0	23-11-11	D04227P	13			D00341	B			YL956-YL999, YN236-YR328
0014	18		PA		8-1	23-11-11	D00341	L	18		D04227P	14			YC051-YD170
0014	18		PA		7-11	23-11-11	D00341	L	18		D04227P	14			YL951-YL955, YN231-YN235
0014	18		PA		8-0	23-11-11	D00341	L	18		D04227P	14			YL956-YL999, YN236-YR328
0016	20		PA		8-1	23-11-11	D00341	A			D04227P	16			YC051-YD170
0016	20		PA		7-11	23-11-11	D00341	A			D04227P	16			YL951-YL955, YN231-YN235
0016	20		PA		8-0	23-11-11	D00341	A			D04227P	16			YL956-YL999, YN236-YR328
0017	22		PA		4-2	23-11-11	D00341	X			SP01525	9			YD158-YR328
0018	22		PA		4-2	23-11-11	D00341	Y			SP01523	9			YD158-YR328

WIRE LIST

D280A108

91-21-11

Section W7050

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From				To				Effectivity
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W7061	286A7061				HF-2 COUPLER											
0004	18		PA		1-7	23-11-21		D00629		D	18		GD00887	AC..	E	YD158-YL955, YN231-YN235
0004	18		PA		1-8	23-11-21		D00629		D	18		GD00887	AC..	E	YL956-YL999, YN236-YR328
0005	20		PA		8-2	23-11-21		D00629		F			D04245P	5		YD158-YD170
0005	20		PA		8-3	23-11-21		D00629		F			D04245P	5		YL951-YR328
0006	18		PA		1-6	23-11-21		D00629		G	18		GD00889	DC..	E	YD158-YD170
0006	18		PA		1-7	23-11-21		D00629		G	18		GD00889	DC..	E	YL951-YL955, YN231-YN235
0006	18		PA		1-8	23-11-21		D00629		G	18		GD00889	DC..	E	YL956-YL999, YN236-YR328
0007	20		PA		8-2	23-11-21		D00629		H			D04245P	7		YD158-YD170
0007	20		PA		8-3	23-11-21		D00629		H			D04245P	7		YL951-YR328
0008	22		PA		8-2	23-11-21		D00629		K			D04245P	8		YD158-YD170
0008	22		PA		8-3	23-11-21		D00629		K			D04245P	8		YL951-YR328
0011	20		PA		8-2	23-11-21		D00629		S			D04245P	11		YD158-YD170
0011	20		PA		8-3	23-11-21		D00629		S			D04245P	11		YL951-YR328
0012	20		PA		8-2	23-11-21		D04245P		12			D00629	C-		YD158-YD170
0012	20		PA		8-3	23-11-21		D04245P		12			D00629	C-		YL951-YR328
0013	20		PA		8-2	23-11-21		D04245P		13			D00629	B		YD158-YD170
0013	20		PA		8-3	23-11-21		D04245P		13			D00629	B		YL951-YR328
0014	18		PA		8-2	23-11-21		D00629		L	18		D04245P	14		YD158-YD170
0014	18		PA		8-3	23-11-21		D00629		L	18		D04245P	14		YL951-YR328
0016	20		PA		8-2	23-11-21		D00629		A			D04245P	16		YD158-YD170
0016	20		PA		8-3	23-11-21		D00629		A			D04245P	16		YL951-YR328
0017	22		PA		4-2	23-11-11		D00629		Y			SP01525		9	YD158-YD170
0017	22		PA		4-3	23-11-11		D00629		Y			SP01525		9	YL951-YR328
0018	22		PA		4-2	23-11-11		D00629		X			SP01523		9	YD158-YD170
0018	22		PA		4-3	23-11-11		D00629		X			SP01523		9	YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W7060

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7102	286A7102			ELEVATOR PITOT HEATERS (NN2)											
1001	20	HE	AA	17-4	31-31-14	D10845		2			D04826P	7			ALL
1001Z			AA	0-0	31-31-14	D10845		DED			D04826P	S/R			ALL
2001B	20	HF	GA	14-3	30-31-11	D04826P		4			D11296	=B			ALL
2001R	20	HF	GA	0-0	30-31-11	D04826P		1			D11296	=A			ALL
2001Z			GA	0-0	30-31-11	D04826P		S/R			GD01792	ST..	E		ALL
2002B	20	HF	GB	14-3	30-31-12	D04826P		3			D11302	=B			ALL
2002R	20	HF	GB	0-0	30-31-12	D04826P		2			D11302	=A			ALL
2002Z			GB	0-0	30-31-12	D04826P		S/R			GD01794	ST..	E		ALL
2003B	20	HF	GC	17-4	31-31-14	D10845		4			D04826P	6			ALL
2003R	20	HF	GC	0-0	31-31-14	D10845		5			D04826P	5			ALL
2003Z			GC	0-0	31-31-14	D10845		DED			D04826P	S/R			ALL

WIRE LIST

D280A108

91-21-11

Section W7100

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7122	286A7122			FWD LEFT SIDE, WHEEL WELL AREA											
0501	18		HA		10-2	29-25-11	D46010P	12			D03244	3			YC051-YR323, YR325-YR328
0502	18		HA		10-2	29-25-11	D46010P	11			D03244	2			YC051-YR323, YR325-YR328
0503	18		HA		4-1	29-25-11	GD00318	DC..	E		D03244	1			YC051-YR323, YR325-YR328
0504	20		HA		6-8	27-23-14	D46010P	9			D00814	3			YC051-YR323, YR325-YR328
0505	20		HA		7-11	27-23-14	GD00320	DC..	E		D00814	2			YC051-YR323, YR325-YR328
0506	18		HA		6-11	27-61-11	D46010P	6			D00760	2			YC051-YR323, YR325-YR328
0507	18		HA		6-11	27-61-11	D46010P	7			D00760	3			YC051-YR323, YR325-YR328
0508	18		HA		8-2	27-61-11	GD00320	DC..	E	*2	D00760	1			YC051-YR323, YR325-YR328
0510	18		HA		6-5	27-23-11	D46010P	5			D00818	3			YC051-YR323, YR325-YR328
0511	18		HA		6-5	27-23-11	D46010P	4			D00818	2			YC051-YR323, YR325-YR328
0512	18		HA		7-8	27-23-11	GD00320	DC..	E	*2	D00818	1			YC051-YD152
0512	18		HA		8-0	27-23-11	GD00320	DC..	E	*2	D00818	1			YD153-YR323, YR325-YR328
0518	20		HA		7-4	27-11-11	D46010P	2			D02928	2			YC051-YR323, YR325-YR328
0519	20		HA		7-4	27-11-11	D46010P	3			D02928	3			YC051-YR323, YR325-YR328
0520	20		HA		7-4	27-11-11	D46010P	1			D02928	1			YC051-YR323, YR325-YR328
0521	20		HA		2-9	27-11-11	GD00180	ST..	E		D02928	12			YC051-YR323, YR325-YR328
0522	18		HA		14-4	29-23-11	D46010P	10			SP00112		9		YC051-YR323, YR325-YR328
0530	20		HA		6-11	31-31-15	D00814	1			D46010P	8			YC065-YD152
0530	20		HA		6-3	31-31-15	D00814	1			D46010P	8			YD153-YR323, YR325-YR328
W7124	286A7124			AFT LEFT SIDE, WHEEL WELL AREA											
0501	20		HA		8-6	29-35-11	D46020P	3			D00824	3			YC051-YD152

WIRE LIST
D280A108

91-21-11
Section W7120
Page 1
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7124		286A7124			AFT LEFT SIDE, WHEEL WELL AREA (continued)											
0501		20		HA		8-8	29-35-11	D46020P		3		D00824		3		YD153
0501		20		HA		8-7	29-35-11	D46020P		3		D00824		3		YD154-YD158
0502		18		HA		3-6	29-31-11	GD00340	DC..	E		D00678		1		YC051-YD152
0502		18		HA		3-2	29-31-11	GD00340	DC..	E		D00678		1		YD153
0502		18		HA		3-10	29-31-11	GD00340	DC..	E		D00678		1		YD154-YD158
0503		18		HA		7-7	27-53-11	D46020P		1		D01010		3		YC051-YD152, YD154-YD158
0503		18		HA		7-8	27-53-11	D46020P		1		D01010		3		YD153
0504		18		HA		7-7	27-53-11	D46020P		4		D01010		2		YC051-YD152, YD154-YD158
0504		18		HA		7-8	27-53-11	D46020P		4		D01010		2		YD153
0505		20		HA		4-6	29-35-11	GD00316	DC..	E		D00824		2		YC051-YD152
0505		20		HA		4-2	29-35-11	GD00316	DC..	E		D00824		2		YD153
0505		20		HA		4-11	29-35-11	GD00316	DC..	E		D00824		2		YD154-YD158
0506		18		HA		8-3	29-31-11	D46020P		2		D00678		2		YC051-YD152
0506		18		HA		8-0	29-31-11	D46020P		2		D00678		2		YD153
0506		18		HA		7-11	29-31-11	D46020P		2		D00678		2		YD154-YD158
0507		18		HA		3-3	27-53-11	GD00316	DC..	E		D01010		1		YC051-YD152
0507		18		HA		3-2	27-53-11	GD00316	DC..	E		D01010		1		YD153
0507		18		HA		3-11	27-53-11	GD00316	DC..	E		D01010		1		YD154-YD158
0509		18		HA		4-1	27-81-51	D46020P		5		D10535		1		YC051-YD152
0509		18		HA		3-7	27-81-51	D46020P		5		D10535		1		YD153-YD158
0510		18		HA		4-1	27-81-51	D46020P		6		D10535		2		YC051-YD152
0510		18		HA		3-7	27-81-51	D46020P		6		D10535		2		YD153-YD158
W7126		286A7126			WHEEL WELL AREA											
0501		18		HA		7-3	31-31-15	D46024P		1		D02870		1		YC051-YD152, YD160-YL955, YN231-YN235
0501		18		HA		7-2	31-31-15	D46024P		1		D02870		1		YD153-YD158, YL956-YL968, YN236, YN501-YR328
0502		18		HA		1-9	31-31-15	GD00380	DC..	E		D02870		2		YC051-YD152
0502		18		HA		1-11	31-31-15	GD00380	DC..	E		D02870		2		YD153-YD158
0502		18		HA		2-0	31-31-15	GD00380	DC..	E		D02870		2		YD160-YL968, YN231-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W7120

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7126	286A7126				WHEEL WELL AREA (continued)										
0503	18		HA		7-3	32-41-11	D46024P	4			D02870	4			YC051-YD152, YD160-YL955, YN231-YN235
0503	18		HA		7-2	32-41-11	D46024P	4			D02870	4			YD153-YD158, YL956-YL968, YN236, YN501-YR328
0504	18		HA		1-9	32-41-11	GD00380	DC..	E		D02870	5			YC051-YD152
0504	18		HA		1-11	32-41-11	GD00380	DC..	E		D02870	5			YD153-YD158
0504	18		HA		2-0	32-41-11	GD00380	DC..	E		D02870	5			YD160-YL968, YN231-YN236, YN501-YR328
0521	18		PA		2-1	32-64-12	GD02054	AC..	E		D46008J	3			YC051-YC058
0521	18		PA		2-6	32-64-12	GD02054	AC..	E		D46008J	3			YC059-YD152
0521	18		PA		9-6	32-64-12	GD02070	AC..	E	*	D46008J	3			YD153-YL955, YN231-YN235
0521	18		PA		9-8	32-64-12	GD02070	AC..	E	*	D46008J	3			YL956-YL968, YN236, YN501-YR328
0533	18		PA		2-8	32-31-12	GD02052	AC..	E		D46006J	7			YC051-YD152
0533	18		PA		14-7	32-31-12	GD02070	AC..	E	*	D46006J	7			YD153-YD158, YN231
0533	18		PA		14-9	32-31-12	GD02070	AC..	E	*	D46006J	7			YD160-YL955, YN232-YN235
0533	18		PA		14-11	32-31-12	GD02070	AC..	E	*	D46006J	7			YL956-YL968, YN236, YN501-YR328
2201B	20		HF	KA	2-3	32-41-11	D46024P	12			D00924	2			YC051-YC058
2201B	20		HF	KA	2-0	32-41-11	D46024P	12			D00924	2			YC059-YL968, YN231-YN236, YN501-YR328
2201R	20		HF	KA	0-0	32-41-11	D46024P	11			D00924	1			YC051-YL968, YN231-YN236, YN501-YR328
2201Z				KA	0-0	32-41-11	D46024P	S/R			D00924	S/R			YC051-YL968, YN231-YN236, YN501-YR328
2203B	20		HF	KC	3-10	32-42-11	D46024P	14			D02564	3			YC051-YC058
2203B	20		HF	KC	3-8	32-42-11	D46024P	14			D02564	3			YC059-YL955, YN231-YN235
2203B	20		HF	KC	2-7	32-42-11	D46024P	14			D02564	3			YL956-YL968, YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W7120

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description FT-IN	Diagram	From	Term	Type	Splice	To	Term	Type	Splice	Effectivity
	GA	CO	TY				Equip				Equip				
W7126	286A7126				WHEEL WELL AREA (continued)										
2203R	20	HF	KC		0-0	32-42-11	D46024P		13		D02564		2		YC051-YL968, YN231-YN236, YN501-YR328
2203Z			KC		0-0	32-42-11	D46024P		S/R		D02564		S/R		YC051-YL968, YN231-YN236, YN501-YR328
2204B	20	HF	KD		3-4	32-42-11	D46024P		16		D02566		3		YC051-YC058, YL956-YL968, YN236, YN501-YR328
2204B	20	HF	KD		3-3	32-42-11	D46024P		16		D02566		3		YC059-YL955, YN231-YN235
2204R	20	HF	KD		0-0	32-42-11	D46024P		15		D02566		2		YC051-YL968, YN231-YN236, YN501-YR328
2204Z			KD		0-0	32-42-11	D46024P		S/R		D02566		S/R		YC051-YL968, YN231-YN236, YN501-YR328
2211B	20	M2	KK		14-9	32-41-11	D46024P		18		D46006J		3		YC051-YC058
2211B	20	M2	KK		14-10	32-41-11	D46024P		18		D46006J		3		YC059-YD158, YN231
2211B	20	M2	KK		14-11	32-41-11	D46024P		18		D46006J		3		YD160-YL968, YN232-YN236, YN501-YR328
2211R	20	M2	KK		0-0	32-41-11	D46024P		17		D46006J		1		YC051-YL968, YN231-YN236, YN501-YR328
2211ZI			KK		0-0	32-41-11	D46024P		19		D46006J		2		YC051-YL968, YN231-YN236, YN501-YR328
2211ZO			KK		0-0	32-41-11	D46024P		S/R		D46006J		S/R		YC051-YL968, YN231-YN236, YN501-YR328
2221B	20	HQ	KV		9-4	32-64-12	D46024P		8		D46008J		2		YC051-YC058
2221B	20	HQ	KV		9-9	32-64-12	D46024P		8		D46008J		2		YC059-YL955, YN231-YN235
2221B	20	HQ	KV		9-8	32-64-12	D46024P		8		D46008J		2		YL956-YL968, YN236, YN501-YR328
2221R	20	HQ	KV		0-0	32-64-12	D46024P		7		D46008J		1		YC051-YL968, YN231-YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W7120

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY	Description Fam	Diagram	From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W7126	286A7126	WHEEL WELL AREA (continued)										
2221Z		KV	0-0	32-64-12	D46024P	S/R		D46008J	S/R			YC051-YL968, YN231-YN236, YN501-YR328
2222B	20	HB KW	6-6	32-64-12	D46024P	6		SP00334	9			YC051-YC058
2222B	20	HB KW	8-0	32-64-12	D46024P	6		SP00334	9			YC059-YD152
2222B	20	HB KW	8-11	32-64-12	D46024P	6		SP00334	9			YD153-YL968, YN231-YN236, YN501-YR328
2222R	20	HB KW	0-0	32-64-12	D46024P	5		SP00332	9			YC051-YL968, YN231-YN236, YN501-YR328
2233B	20	HQ LH	14-9	32-31-12	D46024P	10		D46006J	6			YC051-YC058
2233B	20	HQ LH	14-10	32-31-12	D46024P	10		D46006J	6			YC059-YD158, YN231
2233B	20	HQ LH	14-11	32-31-12	D46024P	10		D46006J	6			YD160-YL968, YN232-YN236, YN501-YR328
2233R	20	HQ LH	0-0	32-31-12	D46024P	9		D46006J	5			YC051-YL968, YN231-YN236, YN501-YR328
2233Z		LH	0-0	32-31-12	D46024P	S/R		D46006J	S/R			YC051-YL968, YN231-YN236, YN501-YR328
A-B			0-0	32-64-12	SP00334	9		S01016	BLU			YC051-YL968, YN231-YN236, YN501-YR328
A-R			0-0	32-64-12	SP00332	9		S01016	RED			YC051-YL968, YN231-YN236, YN501-YR328
A-Y			0-0	32-64-12	GD01948	AC.. E		S01016	YEL			YC051-YD152
A-Y			0-0	32-64-12	GD01962	AC.. E		S01016	YEL			YD153-YL968, YN231-YN236, YN501-YR328
W7128	286A7128	AFT LEFT SIDE WHEEL WELL AREA										
0301	16	CQ	7-1	27-53-12	D46036P	1		D01012	1			YD160-YL955, YN231-YN235
0301	16	CQ	7-0	27-53-12	D46036P	1		D01012	1			YL956-YL999, YN236, YN501-YR328

WIRE LIST
D280A108

91-21-11
Section W7120
Page 5
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7128	286A7128			AFT LEFT SIDE WHEEL WELL AREA (continued)											
0302	16		CQ		7-1	27-53-12	D46036P		2		D01012	2			YD160-YL955, YN231-YN235
0302	16		CQ		7-0	27-53-12	D46036P		2		D01012	2			YL956-YL999, YN236, YN501-YR328
0303	16		CQ		7-1	27-53-12	D46036P		3		D01012	3			YD160-YL955, YN231-YN235
0303	16		CQ		7-0	27-53-12	D46036P		3		D01012	3			YL956-YL999, YN236, YN501-YR328
0304	16		CQ		3-9	27-53-12	GD00302	AC..	E		D01012	4			YD160-YN236, YN501-YR328
0401	20		CQ		8-7	29-35-11	D46020P		3		D00824	3			YD160-YN236, YN501-YR328
0402	18		CQ		3-10	29-31-11	GD00340	DC..	E		D00678	1			YD160-YN236, YN501-YR328
0403	18		CQ		7-7	27-53-11	D46020P		7		D01010	3			YD160-YN236, YN501-YR328
0404	18		CQ		7-7	27-53-11	D46020P		4		D01010	2			YD160-YN236, YN501-YR328
0405	20		CQ		4-11	29-35-11	GD00316	DC..	E		D00824	2			YD160-YN236, YN501-YR328
0406	20		CQ		7-11	29-31-11	D46020P		2		D00678	2			YD160-YN236, YN501-YR328
0407	18		CQ		3-11	27-53-11	GD00316	DC..	E		D01010	1			YD160-YN236, YN501-YR328
0409	20		CQ		3-7	27-81-51	D46020P		5		D10535	1			YD160-YN236, YN501-YR328
0410	20		CQ		3-7	27-81-51	D46020P		6		D10535	2			YD160-YN236, YN501-YR328
0501	20		HA		7-6	29-31-11	D46032P		1		D00674	1			YD160-YN236, YN501-YR328
0502	20		HA		7-6	29-31-11	D46032P		2		D00674	2			YD160-YN236, YN501-YR328
0503	20		HA		7-6	29-31-11	D46032P		3		D00674	3			YD160-YN236, YN501-YR328
0510	20		HA		5-1	29-31-11	GD00304	ST..	E		D00674	5			YD160-YN236, YN501-YR328
0511	18		HA		3-10	32-44-11	D46032P		8		D00928	3			YD160-YL955, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W7120

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7128	286A7128				AFT LEFT SIDE WHEEL WELL AREA (continued)										
0511	18		HA		3-9	32-44-11	D46032P		8		D00928	3			YL956-YL999, YN236, YN501-YR328
0512	18		HA		3-2	32-44-11	GD00308	DC..	E		D00928	1			YD160-YN236, YN501-YR328
0513	18		HA		3-10	32-44-11	D46032P		7		D00928	2			YD160-YL955, YN231-YN235
0513	18		HA		3-9	32-44-11	D46032P		7		D00928	2			YL956-YL999, YN236, YN501-YR328
0514	18		HA		3-10	32-44-11	D46032P		10		D00928	8			YD160-YL955, YN231-YN235
0514	18		HA		3-9	32-44-11	D46032P		10		D00928	8			YL956-YL999, YN236, YN501-YR328
0515	18		HA		3-2	32-44-11	GD00308	DC..	E		D00928	9			YD160-YN236, YN501-YR328
0516	18		HA		3-10	32-44-11	D46032P		11		D00928	10			YD160-YL955, YN231-YN235
0516	18		HA		3-9	32-44-11	D46032P		11		D00928	10			YL956-YL999, YN236, YN501-YR328
0517	18		HA		3-10	32-44-11	D46032P		9		D00928	4			YD160-YL955, YN231-YN235
0517	18		HA		3-9	32-44-11	D46032P		9		D00928	4			YL956-YL999, YN236, YN501-YR328
0518	18		CQ		6-7	27-23-11	D46032P		12		D00822	2			YD160-YL955, YN231-YN235
0518	18		CQ		6-6	27-23-11	D46032P		12		D00822	2			YL956-YL999, YN236, YN501-YR328
0519	18		CQ		6-7	27-23-11	D46032P		13		D00822	3			YD160-YL955, YN231-YN235
0519	18		CQ		6-6	27-23-11	D46032P		13		D00822	3			YL956-YL999, YN236, YN501-YR328
0520	18		CQ		6-7	27-23-14	D46032P		14		D00822	4			YD160-YL955, YN231-YN235
0520	18		CQ		6-6	27-23-14	D46032P		14		D00822	4			YL956-YL999, YN236, YN501-YR328
0521	18		CQ		3-1	27-23-11	GD00316	DC..	E		D00822	1			YD160-YN236, YN501-YR328
2201B	18		HF	KA	4-6	32-41-11	D46032P		5		D00926	2			YD160-YL955, YN231-YN235
2201B	18		HF	KA	3-11	32-41-11	D46032P		5		D00926	2			YL956-YL959

WIRE LIST
D280A108

91-21-11
Section W7120
Page 7
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To							
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7128	286A7128			AFT LEFT SIDE WHEEL WELL AREA (continued)											
2201B	18		HF	KA	3-10	32-41-11	D46032P	5			D00926	2			YL963-YL999, YN236, YN501-YR328
2201R	18		HF	KA	0-0	32-41-11	D46032P	4			D00926	1			YD160-YN236, YN501-YR328
2201Z				KA	0-0	32-41-11	D46032P	S/R			D00926	S/R			YD160-YN236, YN501-YR328
3001B	20		X3	BA	7-0	31-31-14	D46020P	11			D11995	3			YD160-YL955, YN231-YN235
3001B	20		X3	BA	6-11	31-31-14	D46020P	11			D11995	3			YL956-YL959
3001B	20		X3	BA	6-10	31-31-14	D46020P	11			D11995	3			YL963-YL999, YN236, YN501-YR328
3001R	20		X3	BA	0-0	31-31-14	D46020P	9			D11995	2			YD160-YN236, YN501-YR328
3001Y	20		X3	BA	0-0	31-31-14	D46020P	12			D11995	1			YD160-YN236, YN501-YR328
3001Z				BA	0-0	31-31-14	D46020P	8	18		D11995	DED			YD160-YN236, YN501-YR328
6001R	20		9P		9-4	26-12-11	D46032P	6			D00854	= 1			YD160-YL955, YN231-YN235
6001R	20		9P		9-3	26-12-11	D46032P	6			D00854	= 1			YL956-YL959
6001R	20		9P		9-2	26-12-11	D46032P	6			D00854	= 1			YL963-YL999, YN236, YN501-YR328

WIRE LIST

D280A108

91-21-11

Section W7120

Page 8 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7134	286A7134				#1 LEFT GEAR ON GROUND/OUTBD ANTISKID XDCR										
2201B	20	Y6	KA		0-0	32-41-11	D11120		3		TB0002K	G002	1		ALL
2201R	20	Y6	KA		0-0	32-41-11	D11120		1		TB0002K	E002	1		ALL
2201Z			KA		0-0	32-41-11	D11120		DED		TB0002L	A003	1		ALL
2211B	18	HQ	KK		0-0	32-41-11	D46004P		3		TB0002K	G002	1		ALL
2211R	18	HQ	KK		0-0	32-41-11	D46004P		1		TB0002K	E002	1		ALL
2211Z			KK		0-0	32-41-11	D46004P		2		TB0002L	A003	1		ALL
3201B	18	HN	YA		0-0	32-31-11	D46004P		6		TB0002K	C001	1		ALL
3201R	18	HN	YA		0-0	32-31-11	D46004P		5		TB0002K	A001	1		ALL
3201Y	18	HN	YA		0-0	32-31-11	D46004P		7		TB0002K	E001	1		ALL
A-B					0-0	32-31-11	TB0002K		C001	1	S01012	BLU			ALL
A-R					0-0	32-31-11	TB0002K		A001	1	S01012	RED			ALL
A-Y					0-0	32-31-11	TB0002K		E001	1	S01012	YEL			ALL
W7136	286A7136				#2 LEFT GEAR ON GROUND/INBD ANTISKID XDCR										
2201B	20	Y6	KA		0-0	32-41-11	D11122		3		TB0004K	G002	1		ALL
2201R	20	Y6	KA		0-0	32-41-11	D11122		1		TB0004K	E002	1		ALL
2201Z			KA		0-0	32-41-11	D11122		DED		TB0004L	A003	1		ALL
2211B	18	HQ	KK		0-0	32-41-11	D46006P		3		TB0004K	G002	1		ALL
2211R	18	HQ	KK		0-0	32-41-11	D46006P		1		TB0004K	E002	1		ALL
2211Z			KK		0-0	32-41-11	D46006P		2		TB0004L	A003	1		ALL
3201B	18	HN	YA		0-0	32-31-12	D46006P		6		TB0004K	C001	1		ALL
3201R	18	HN	YA		0-0	32-31-12	D46006P		5		TB0004K	A001	1		ALL
3201Y	18	HN	YA		0-0	32-31-12	D46006P		7		TB0004K	E001	1		ALL
A-B					0-0	32-31-12	TB0004K		C001	1	S01013	BLU			ALL
A-R					0-0	32-31-12	TB0004K		A001	1	S01013	RED			ALL
A-Y					0-0	32-31-12	TB0004K		E001	1	S01013	YEL			ALL
W7137	286A7137				VOR ANTENNA LEFT - STA 1035 TO RF PWR DIV-1										
001CO			AA		0-0	34-51-11	D03699		= C1		D04435J	= C1			ALL
001CX		0H	AA		127-5	34-51-11	D03699		= A1		D04435J	= A1			YC051-YC052
001CX		0H	AA		128-1	34-51-11	D03699		= A1		D04435J	= A1			YC053-YC055
001CX		0H	AA		128-2	34-51-11	D03699		= A1		D04435J	= A1			YC056-YD158
001CX		0H	AA		128-4	34-51-11	D03699		= A1		D04435J	= A1			YD160-YL999, YR301-YR328
001CX		0H	AA		108-8	34-51-11	D03699		= A1		D04435J	= A1			YN231-YN501

WIRE LIST

D280A108

91-21-11
Section W7130
Page 1 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W7150	286A7150	TAIL CONE DISC. TO TAIL NAV LIGHT													
1201	18	HP	DA	2-3	33-35-11	D44584J	1		S00099	1	G7			YC051-YL968, YN231-YN235	
1201	18	HP	DA	2-4	33-35-11	D44584J	1		S00099	1	G7			YN236-YR328	
1201Z			DA	0-0	33-35-11	D44584J	S/R		S00099			FA		YC051-YL968, YN231-YR328	
1202	18	HP	DB	10-3	33-35-11	D44584J	2		L00278	=G	G7			YC051-YL968, YN231-YR328	
1202Z			DB	0-0	33-35-11	D44584J	S/R		L00278	DED				YC051-YL968, YN231-YR328	
1203	18	HP	DC	9-0	33-35-11	L00278	=P	BK	S00099	2	G7			YC051-YL968, YN231-YR328	
1203Z			DC	0-0	33-35-11	S00099								YC051-YL968, YN231-YR328	
2403B	20	HQ	OC	11-11	33-44-12	D44584J	4		D00148	D				YC051-YL968, YN231-YN235	
2403R	20	HQ	OC	0-0	33-44-12	D44584J	3		D00148	B				YC051-YL968, YN231-YN235	
2403Z			OC	0-0	33-44-12	D44584J	S/R		D00148	DED				YC051-YL968, YN231-YN235	
W7152	286A7152	TAIL STROBE DISC. TO TAIL NAV LIGHT													
2001B	20	M2	EA	7-7	33-44-12	D44582J	2		D00148	D				YL969-YL999, YN236, YN501-YR328	
2001R	20	M2	EA	0-0	33-44-12	D44582J	1		D00148	B				YL969-YL999, YN236, YN501-YR328	
2001ZI			EA	0-0	33-44-12	D44582J	PERB		D00148	PERB				YL969-YL999, YN236, YN501-YR328	
2001ZO			EA	0-0	33-44-12	D44582J	PERB		D00148	PERB				YL969-YL999, YN236, YN501-YR328	
YAAA				0-0	33-44-12	D44582J	PERB		D00148	PERB				YL969-YL999, YN236, YN501-YR328	
W7153	286A7153	VOR ANT LEFT - XMSN CABLE													
001CO			AA	0-0	34-51-11	D00089	=C1		D04435P	=C1				ALL	
001CX		OH	AA	30-10	34-51-11	D00089	=A1		D04435P	=A1				ALL	
W7157	286A7157	LOCALIZER ANTENNA LEFT - STA 178 TO ANTENNA													
001CO			AA	0-0	34-31-11	D02129	=C1		D03313	=C1				ALL	

WIRE LIST

D280A108

91-21-11

Section W7150

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7157	286A7157			LOCALIZER ANTENNA LEFT - STA 178 TO ANTENNA (continued)											
001CX			0F	AA	1-6	34-31-11	D02129	=	A1		D03313	=	A1		ALL
W7159	286A7159			G/S ANT LEFT - STA 178 TO ANT											
001CO				AA	0-0	34-31-11	D00085	=	C1		D03309	=	C1		ALL
001CX			0F	AA	3-1	34-31-11	D00085	=	A1		D03309	=	A1		YC051-YC063
001CX			0F	AA	7-1	34-31-11	D00085	=	A1		D03309	=	A1		YC064-YR328

WIRE LIST
D280A108

91-21-11
Section W7150
Page 2 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity

I	W7187	286A7187				MARKER BEACON ANTENNA - EE BAY TO STA 610 (D4119)										
I	001CO				AA	0-0	34-32-11	D04119J	=	C1		D04121J	=	C1		ALL
I	001CX			0F	AA	48-0	34-32-11	D04119J	=	A1		D04121J	=	A1		YC051-YC064
I	001CX			0F	AA	48-1	34-32-11	D04119J	=	A1		D04121J	=	A1		YC065-YL999,
	001CX			0F	AA	38-3	34-32-11	D04119J	=	A1		D04121J	=	A1		YR301-YR328 YN231-YN501

WIRE LIST

D280A108

91-21-11

Section W7180

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I W7193	286A7193			MARKER BEACON ANTENNA - STA 610 (D4119) TO ANTENNA											
I 001CO				AA	0-0	34-32-11	D04119P		= C1		D00057		= C1		ALL
I 001CX		0F		AA	1-3	34-32-11	D04119P		= A1		D00057		= A1		ALL

For training purposes only!

WIRE LIST
D280A108

91-21-11
Section W7190
Page 1 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7202	286A7202			BULKHEAD PRESS SEAL TO NGS EQUIPMENT											
0010	22		HA		0-6	47-30-11	D13820		3		SM00011		9		YL951-YL999, YN232-YR328
0011	22		HA		0-6	47-30-11	D13810		D		SM00002		9		YL951-YL999, YN232-YR328
0012	22		HA		0-6	47-30-11	D13816		C		SM00003		9		YL951-YL999, YN232-YR328
0013	22		HA		0-6	47-30-11	D13826		B		SM00004		9		YL951-YL999, YN232-YR328
0014	22		HA		0-6	47-30-11	D14200		C		SM00005		9		YL951-YL999, YN232-YR328
0015	22		HA		0-11	47-30-11	D13830		5		SM00006		9		YL951-YL999, YN232-YR328
0016	22		HA		0-15	47-30-11	D13824		5		SM00007		9		YL951-YL999, YN232-YR328
0017	22		HA		0-12	47-30-11	D13818		5		SM00008		9		YL951-YL999, YN232-YR328
0018	22		HA		0-6	47-30-11	D13828		E		SM00009		9		YL951-YL999, YN232-YR328
0019	22		HA		0-6	47-30-11	D13812		C		SM00010		9		YL951-YL999, YN232-YR328
0020	16		HA		1-6	47-30-11	SM00011		9		GD00111	ST..	N		YL951-YL999, YN232-YR328
0021	16		HA		1-2	47-30-11	SM00002		9		GD02318	ST..	N		YL951-YL999, YN232-YR328
0022	16		HA		3-1	47-30-11	SM00003		9		GD00109	ST..	N	*	YL951-YL999, YN232-YR328
0023	16		HA		2-4	47-30-11	SM00004		9		GD00109	ST..	N	*	YL951-YL999, YN232-YR328
0024	16		HA		1-4	47-30-11	SM00005		9		GD00129	ST..	N		YL951-YL999, YN232-YR328
0025	16		HA		1-5	47-30-11	SM00006		9		GD02318	ST..	N		YL951-YL999, YN232-YR328
0026	16		HA		1-2	47-30-11	SM00007		9		GD00111	ST..	N		YL951-YL999, YN232-YR328
0027	16		HA		1-4	47-30-11	SM00008		9		GD00109	ST..	N	*1	YL951-YL999, YN232-YR328
0028	16		HA		3-4	47-30-11	SM00009		9		GD00109	ST..	N	*1	YL951-YL999, YN232-YR328

WIRE LIST

D280A108

91-21-11

Section W7200

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description Fam	Diagram	From	To			Effectivity					
	GA	CO	TY			Equip	Term	Type	Splice		Equip	Term	Type	Splice	
W7202	286A7202			BULKHEAD PRESS SEAL TO NGS EQUIPMENT (continued)											
0029	16		HA		1-6	47-30-11	SM00010		9		GD00113	ST..	N		YL951-YL999, YN232-YR328
1201	20		HP	BA	17-9	47-30-11	D13932		19		D13820	2			YL951-YL999, YN232-YR328
1201Z				BA	0-0	47-30-11	D13932		PERB		D13820	PERB			YL951-YL999, YN232-YR328
1202	20		HP	BB	13-4	47-30-11	D13820		1		SM00001		9		YL951-YL999, YN232-YR328
1202Z				BB	0-0	47-30-11	D13820		PERB		SM00014		9		YL951-YL999, YN232-YR328
1203	20		HP	BC	4-10	47-30-11	D13810		A		SM00001		9		YL951-YL999, YN232-YR328
1203Z				BC	0-0	47-30-11	D13810		PERB		SM00014		9		YL951-YL999, YN232-YR328
1204	20		HP	BD	2-1	47-30-11	D13932		39		D13810	B			YL951-YL999, YN232-YR328
1204Z				BD	0-0	47-30-11	D13932		PERB		D13810	PERB			YL951-YL999, YN232-YR328
1205	20		HP	BE	4-11	47-30-11	D13932		6		SM00001		9		YL951-YL999, YN232-YR328
1205Z				BE	0-0	47-30-11	D13932		PERB		SM00014		9		YL951-YL999, YN232-YR328
1206	20		HP	BF	10-1	47-30-11	D13816		A		SM00001		9		YL951-YL999, YN232-YR328
1206Z				BF	0-0	47-30-11	D13816		PERB		SM00014		9		YL951-YL999, YN232-YR328
1207	20		HP	BG	3-4	47-30-11	D13816		B		D13826	A			YL951-YL999, YN232-YR328
1207Z				BG	0-0	47-30-11	D13816		PERB		D13826	PERB			YL951-YL999, YN232-YR328
1208	20		HP	BH	13-9	47-30-11	D13932		38		D13826	C			YL951-YL999, YN232-YR328
1208Z				BH	0-0	47-30-11	D13932		PERB		D13826	PERB			YL951-YL999, YN232-YR328
1209	20		HP	BJ	2-5	47-30-11	D14200		F		SM00001		9		YL951-YL999, YN232-YR328
1209Z				BJ	0-0	47-30-11	D14200		PERB		SM00014		9		YL951-YL999, YN232-YR328

WIRE LIST
D280A108

91-21-11
Section W7200
Page 2
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7202	286A7202			BULKHEAD PRESS SEAL TO NGS EQUIPMENT (continued)											
1210	20	HP	BK		5-2	47-30-11	D13932	24			D14200	G			YL951-YL999, YN232-YR328
1210Z			BK		0-0	47-30-11	D13932	PERB			D14200	PERB			YL951-YL999, YN232-YR328
1211	20	HP	BL		5-2	47-30-11	D13932	36			D14200	E			YL951-YL999, YN232-YR328
1211Z			BL		0-0	47-30-11	D13932	PERB			D14200	PERB			YL951-YL999, YN232-YR328
1212	20	HP	BM		5-2	47-30-11	D13932	15			D14200	D			YL951-YL999, YN232-YR328
1212Z			BM		0-0	47-30-11	D13932	PERB			D14200	PERB			YL951-YL999, YN232-YR328
2501B	20	HQ	AA		1-10	47-30-11	D13932	4			SM00012		9		YL951-YL999, YN232-YR328
2501R	20	HQ	AA		0-0	47-30-11	D13932	13			SM00013		9		YL951-YL999, YN232-YR328
2501Z			AA		0-0	47-30-11	D13932	PERB			SM00REF	12			YL951-YL999, YN232-YR328
2502B	20	HQ	AB		16-9	47-30-11	D13932	30			SM00018		9		YL951-YL999, YN232-YR328
2502R	20	HQ	AB		0-0	47-30-11	D13932	31			SM00015		9		YL951-YL999, YN232-YR328
2502Z			AB		0-0	47-30-11	D13932	PERB			SM00REF	18			YL951-YL999, YN232-YR328
2503B	20	HQ	AC		12-4	47-30-11	D13932	32			SM00016		9		YL951-YL999, YN232-YR328
2503R	20	HQ	AC		0-0	47-30-11	D13932	33			SM00017		9		YL951-YL999, YN232-YR328
2503Z			AC		0-0	47-30-11	D13932	PERB			SM00REF	16			YL951-YL999, YN232-YR328
2504B	20	HQ	AD		14-9	47-30-11	D13932	26			D13828	A			YL951-YL999, YN232-YR328
2504R	20	HQ	AD		0-0	47-30-11	D13932	27			D13828	D			YL951-YL999, YN232-YR328
2504Z			AD		0-0	47-30-11	D13932	PERB			D13828	PERB			YL951-YL999, YN232-YR328
2505B	20	HQ	AE		14-9	47-30-11	D13932	28			D13828	B			YL951-YL999, YN232-YR328

WIRE LIST

D280A108

91-21-11

Section W7200

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Description Fam FT-IN Diagram		From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W7202	286A7202			BULKHEAD PRESS SEAL TO NGS EQUIPMENT (continued)										
2505R	20	HQ	AE	0-0	47-30-11	D13932	29			D13828	C			YL951-YL999, YN232-YR328
2505Z			AE	0-0	47-30-11	D13932	PERB			D13828	PERB			YL951-YL999, YN232-YR328
2506B	20	HQ	AF	14-6	47-30-11	D13932	21			D13812	B			YL951-YL999, YN232-YR328
2506R	20	HQ	AF	0-0	47-30-11	D13932	20			D13812	A			YL951-YL999, YN232-YR328
2506Z			AF	0-0	47-30-11	D13932	PERB			D13812	PERB			YL951-YL999, YN232-YR328
2507B	20	HQ	AG	14-10	47-30-11	D13932	8			D13814	A			YL951-YL999, YN232-YR328
2507R	20	HQ	AG	0-0	47-30-11	D13932	18			D13814	B			YL951-YL999, YN232-YR328
2507Z			AG	0-0	47-30-11	D13932	PERB			D13814	PERB			YL951-YL999, YN232-YR328
2508B	22	HF	AH	0-11	47-30-11	SM00012	9			D13830	1			YL951-YL999, YN232-YR328
2508R	22	HF	AH	0-0	47-30-11	SM00013	9			D13830	3			YL951-YL999, YN232-YR328
2508Z			AH	0-0	47-30-11	SM00REF	12			D13830	PERB			YL951-YL999, YN232-YR328
2509B	22	HF	AI	0-15	47-30-11	SM00018	9			D13824	1			YL951-YL999, YN232-YR328
2509R	22	HF	AI	0-0	47-30-11	SM00015	9			D13824	3			YL951-YL999, YN232-YR328
2509Z			AI	0-0	47-30-11	SM00REF	18			D13824	PERB			YL951-YL999, YN232-YR328
2510B	22	HF	AJ	0-12	47-30-11	SM00016	9			D13818	1			YL951-YL999, YN232-YR328
2510R	22	HF	AJ	0-0	47-30-11	SM00017	9			D13818	3			YL951-YL999, YN232-YR328
2510Z			AJ	0-0	47-30-11	SM00REF	16			D13818	PERB			YL951-YL999, YN232-YR328
W7208	286A7208			BULKHEAD PRESS SEAL TO NGS BITE DISPLAY UNIT										
0099	20	HA		1-11	47-30-11	D13808	4			GD00095	ST..	N		YL951-YL999, YN232-YR328

WIRE LIST
D280A108

91-21-11
Section W7200
Page 4
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7208	286A7208			BULKHEAD PRESS SEAL TO NGS BITE DISPLAY UNIT (continued)											
1001	20		HP	AD	2-3	47-30-11	D13808		7		D13972		4		YL951-YL999, YN232-YR328
1001Z				AD	0-0	47-30-11	D13808		PERB		D13972		PERB		YL951-YL999, YN232-YR328
2001B	20		HQ	AC	2-3	47-30-11	D13808		10		D13972		39		YL951-YL999, YN232-YR328
2001R	20		HQ	AC	0-0	47-30-11	D13808		11		D13972		20		YL951-YL999, YN232-YR328
2001Z				AC	0-0	47-30-11	D13808		PERB		D13972		PERB		YL951-YL999, YN232-YR328
3001B	20		HR	AB	2-3	47-30-11	D13808		12		D13972		36		YL951-YL999, YN232-YR328
3001R	20		HR	AB	0-0	47-30-11	D13808		8		D13972		34		YL951-YL999, YN232-YR328
3001Y	20		HR	AB	0-0	47-30-11	D13808		6		D13972		32		YL951-YL999, YN232-YR328
3001Z				AB	0-0	47-30-11	D13808		PERB		D13972		PERB		YL951-YL999, YN232-YR328
4001B	20		HS	AA	2-3	47-30-11	D13808		3		D13972		22		YL951-YL999, YN232-YR328
4001G	20		HS	AA	0-0	47-30-11	D13808		2		D13972		24		YL951-YL999, YN232-YR328
4001R	20		HS	AA	0-0	47-30-11	D13808		1		D13972		26		YL951-YL999, YN232-YR328
4001Y	20		HS	AA	0-0	47-30-11	D13808		9		D13972		28		YL951-YL999, YN232-YR328
4001Z				AA	0-0	47-30-11	D13808		PERB		D13972		PERB		YL951-YL999, YN232-YR328

WIRE LIST

D280A108

91-21-11

Section W7200

Page 5 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I W7222	286A7222			AFT LEFT SIDE WHEEL WELL AREA											
	0501	16	HA	7-0	27-53-12	D46036P		1			D01012	1			YC051-YD152
	0501	16	HA	7-3	27-53-12	D46036P		1			D01012	1			YD153
I	0501	16	HA	7-2	27-53-12	D46036P		1			D01012	1			YD154-YD158
	0502	16	HA	7-0	27-53-12	D46036P		2			D01012	2			YC051-YD152
	0502	16	HA	7-3	27-53-12	D46036P		2			D01012	2			YD153
I	0502	16	HA	7-2	27-53-12	D46036P		2			D01012	2			YD154-YD158
	0503	16	HA	7-0	27-53-12	D46036P		3			D01012	3			YC051-YD152
	0503	16	HA	7-3	27-53-12	D46036P		3			D01012	3			YD153
I	0503	16	HA	7-2	27-53-12	D46036P		3			D01012	3			YD154-YD158
	0504	16	HA	3-0	27-53-12	GD00302		AC..	E		D01012	4			YC051-YD152
	0504	16	HA	3-1	27-53-12	GD00302		AC..	E		D01012	4			YD153
I	0504	16	HA	3-10	27-53-12	GD00302		AC..	E		D01012	4			YD154-YD158

WIRE LIST
D280A108

91-21-11
Section W7220
Page 1 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7230	286A7230			FWD LEFT SIDE WHEEL WELL AREA											
0501	18		HA		7-5	29-32-11	D46028P		2		D00662		3		YC051-YC055
0501	18		HA		7-6	29-32-11	D46028P		2		D00662		3		YC056-YD152
0501	18		HA		10-3	29-32-11	D46028P		2		D00662		3		YD153-YR323, YR325-YR328
0502	18		HA		7-5	29-32-11	D46028P		1		D00662		2		YC051-YC055
0502	18		HA		7-6	29-32-11	D46028P		1		D00662		2		YC056-YD152
0502	18		HA		10-3	29-32-11	D46028P		1		D00662		2		YD153-YR323, YR325-YR328
0503	18		HA		2-10	29-32-11	GD00490	ST..	E		D00662		1		YC051-YD152
0503	18		HA		2-11	29-32-11	GD01964	ST..	E		D00662		1		YD153-YL963, YN231-YN235
0503	18		HA		3-0	29-32-11	GD01964	ST..	E		D00662		1		YL964-YL999, YN236-YR323, YR325-YR328
0521	18		PA		2-11	32-64-11	GD02056	AC..	E		D46002J		3		YC051-YD152
0521	18		PA		12-11	32-64-11	GD02074	AC..	E		D46002J		3		YD153-YR323, YR325-YR328
0533	18		PA		2-8	32-31-11	GD02056	AC..	E		D46004J		7		YC051-YD152
0533	18		PA		12-9	32-31-11	GD02074	AC..	E		D46004J		7		YD153-YR323, YR325-YR328
2211B	20		M2	KK	10-7	32-41-11	D46028P		7		D46004J		3		YC051-YC055
2211B	20		M2	KK	10-6	32-41-11	D46028P		7		D46004J		3		YC056-YD152
2211B	20		M2	KK	11-7	32-41-11	D46028P		7		D46004J		3		YD153-YR323, YR325-YR328
2211R	20		M2	KK	0-0	32-41-11	D46028P		6		D46004J		1		YC051-YR323, YR325-YR328
2211ZI				KK	0-0	32-41-11	D46028P		8		D46004J		2		YC051-YR323, YR325-YR328
2211ZO				KK	0-0	32-41-11	D46028P		S/R		D46004J		S/R		YC051-YR323, YR325-YR328
2221B	20		HQ	KV	10-10	32-64-11	D46028P		10		D46002J		2		YC051-YC055
2221B	20		HQ	KV	10-9	32-64-11	D46028P		10		D46002J		2		YC056-YD152
2221B	20		HQ	KV	11-9	32-64-11	D46028P		10		D46002J		2		YD153-YD157
2221B	20		HQ	KV	11-10	32-64-11	D46028P		10		D46002J		2		YD158-YR323, YR325-YR328
2221R	20		HQ	KV	0-0	32-64-11	D46028P		9		D46002J		1		YC051-YR323, YR325-YR328
2221Z				KV	0-0	32-64-11	D46028P		S/R		D46002J		S/R		YC051-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W7230

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7230	286A7230			FWD LEFT SIDE WHEEL WELL AREA (continued)											
2222B	20	HB	KW		10-3	32-64-11	D46028P		5		SP00344		9		YC051-YC055
2222B	20	HB	KW		10-2	32-64-11	D46028P		5		SP00344		9		YC056-YD152
2222B	20	HB	KW		11-2	32-64-11	D46028P		5		SP00344		9		YD153-YD157
2222B	20	HB	KW		11-3	32-64-11	D46028P		5		SP00344		9		YD158-YR323, YR325-YR328
2222R	20	HB	KW		0-0	32-64-11	D46028P		4		SP00342		9		YC051-YR323, YR325-YR328
2233B	20	HQ	LH		10-7	32-31-11	D46028P		13		D46004J		6		YC051-YC055
2233B	20	HQ	LH		10-6	32-31-11	D46028P		13		D46004J		6		YC056-YD152
2233B	20	HQ	LH		11-7	32-31-11	D46028P		13		D46004J		6		YD153-YR323, YR325-YR328
2233R	20	HQ	LH		0-0	32-31-11	D46028P		12		D46004J		5		YC051-YR323, YR325-YR328
2233Z			LH		0-0	32-31-11	D46028P		S/R		D46004J		S/R		YC051-YR323, YR325-YR328
6001	20	HA			15-9	28-42-11	D46028P		16		SP00174		9		YC051-YC055
6001	20	HA			15-8	28-42-11	D46028P		16		SP00174		9		YC056-YD152
6001	20	HA			16-9	28-42-11	D46028P		16		SP00174		9		YD153-YR323, YR325-YR328
6002	18	HA			3-1	28-42-11	GD00476	DC..	E		SP00172		9		YC051-YR323, YR325-YR328
6003	20	HA			15-9	28-42-11	D46028P		15		SP00172		9		YC051-YC055
6003	20	HA			15-8	28-42-11	D46028P		15		SP00172		9		YC056-YD152
6003	20	HA			16-9	28-42-11	D46028P		15		SP00172		9		YD153-YR323, YR325-YR328
6011	18	CQ			8-3	28-21-11	D46028P		3		SP00326		9		YC051-YC055
6011	18	CQ			7-10	28-21-11	D46028P		3		SP00326		9		YC056-YD152
6011	18	CQ			10-6	28-21-11	D46028P		3		SP00326		9		YD153-YR323, YR325-YR328
A-AA					0-0	28-42-11	T00434		= A		SP00172		9		YC051-YR323, YR325-YR328
A-B					0-0	32-64-11	S00072		BLU		SP00344		9		YC051-YR323, YR325-YR328
A-R					0-0	32-64-11	S00072		RED		SP00342		9		YC051-YR323, YR325-YR328
A-Y					0-0	32-64-11	S00072		YEL		GD01948	AC..	E		YC051-YR323, YR325-YR328
B-BB					0-0	28-42-11	T00434		= B		SP00174		9		YC051-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W7230

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type		Splice	
W7359	286A7359				AFT CAB/APU SERVICE INTERPHONE											
0001	18		PA		4-0	35-21-21	D07172P		= 1	VG		D40032P	1			YC051-YL999, YR301-YR328
0001	18		PA		3-9	35-21-21	D07172P		= 1	VG		D40032P	1			YN231-YN501
0002	18		PA		2-10	35-21-21	GD03948		DC..	1		D40032P	2			ALL
3501B	20		X3	AA	79-0	23-41-11	TB0205W		B001	1		SM00002		9		YC051-YL999, YR301-YR328
3501B	20		X3	AA	68-5	23-41-11	TB0205W		B001	1		SM00002		9		YN231-YN501
3501R	20		X3	AA	0-0	23-41-11	TB0205W		A001	1		SM00001		9		ALL
3501Y	20		X3	AA	0-0	23-41-11	TB0205W		A005	1		SM00003		9		ALL
3501Z				AA	0-0	23-41-11	TB0205W		B005	1		SM00004		9		ALL
3502B	20		X3	AB	26-4	23-41-11	SM00002			9		SP00049		9		YC051-YL999, YR301-YR328
3502B	20		X3	AB	25-8	23-41-11	SM00002			9		SP00049		9		YN231-YN501
3502R	20		X3	AB	0-0	23-41-11	SM00001			9		SP00047		9		ALL
3502Y	20		X3	AB	0-0	23-41-11	SM00003			9		SP00051		9		ALL
3502Z				AB	0-0	23-41-11	SM00004			9		SP00047		DED		ALL
3503B	20		X3	AC	1-2	23-41-11	SM00002			9		D40032P		5		ALL
3503R	20		X3	AC	0-0	23-41-11	SM00001			9		D40032P		4		ALL
3503Y	20		X3	AC	0-0	23-41-11	SM00003			9		D40032P		3		ALL
3503Z				AC	0-0	23-41-11	SM00004			9		D40032P		DED		ALL
A-A					0-0	23-41-11	SP00047			9		D06017		RED		ALL
A-B					0-0	23-41-11	SP00049			9		D06017		BLU		ALL
A-C					0-0	23-41-11	SP00051			9		D06017		BLK		ALL

WIRE LIST

D280A108

91-21-11

Section W7350

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7381	286A7381				AB1050L, AB1050R TO RUDDER POSN SENSOR, RUDDER ACTUATOR										
1001	20	HE	A		6-7	22-11-81	D11617	14			GD00015	DC..	E	*1	YC064-YC070
1001	20	HE	A		7-0	22-11-81	D11617	14			GD00015	DC..	E	*	YD151-YD158, YL951-YR328
1001Z			A		0-0	22-11-81	D11617	S/R			GD00015	DC..	E	*1	YC064-YC070
1001Z			A		0-0	22-11-81	D11617	S/R			GD00015	DC..	E	*	YD151-YD158, YL951-YR328
1002	20	HE	B		6-7	22-11-81	D11617	20			GD00015	DC..	E	*1	YC064-YC070
1002	20	HE	B		7-0	22-11-81	D11617	20			GD00015	DC..	E	*	YD151-YD158, YL951-YR328
1002Z			B		0-0	22-11-81	D11617	S/R			GD00015	DC..	E	*1	YC064-YC070
1002Z			B		0-0	22-11-81	D11617	S/R			GD00015	DC..	E	*	YD151-YD158, YL951-YR328
1003	20	HE	C		6-7	22-11-81	D11619	14			GD00015	DC..	E	*2	YC064-YC070
1003Z			C		0-0	22-11-81	D11619	S/R			GD00015	DC..	E	*2	YC064-YC070
1004	20	HE	D		6-7	22-11-81	D11619	20			GD00015	DC..	E	*2	YC064-YC070
1004Z			D		0-0	22-11-81	D11619	S/R			GD00015	DC..	E	*2	YC064-YC070
2001B	20	HF	AA		19-4	22-11-81	D45501J	2			D11617	1			YC064
2001B	20	HF	AA		19-2	22-11-81	D45501P	2			D11617	1			YC065-YC070
2001B	20	HF	AA		17-11	22-11-81	D45501P	15			D11617	1			YD151-YD158
2001B	20	HF	AA		18-1	22-11-81	D45501P	15			D11617	1			YL951-YR328
2001R	20	HF	AA		0-0	22-11-81	D45501J	1			D11617	6			YC064
2001R	20	HF	AA		0-0	22-11-81	D45501P	1			D11617	6			YC065-YC070
2001R	20	HF	AA		0-0	22-11-81	D45501P	14			D11617	6			YD151-YD158, YL951-YR328
2001Z			AA		0-0	22-11-81	D45501J	S/R			D11617	S/R			YC064
2001Z			AA		0-0	22-11-81	D45501P	S/R			D11617	S/R			YC065-YD158, YL951-YR328
2002B	18	HF	AB		19-4	22-11-81	D45501J	4	18		D11617	13	18		YC064
2002B	18	HF	AB		19-2	22-11-81	D45501P	4	18		D11617	13	18		YC065-YC070
2002B	18	HF	AB		17-11	22-11-81	D45501P	3	18		D11617	13	18		YD151-YD158
2002B	18	HF	AB		18-1	22-11-81	D45501P	3	18		D11617	13	18		YL951-YR328
2002R	18	HF	AB		0-0	22-11-81	D45501J	3	18		D11617	18	18		YC064
2002R	18	HF	AB		0-0	22-11-81	D45501P	3	18		D11617	18	18		YC065-YC070
2002R	18	HF	AB		0-0	22-11-81	D45501P	1	18		D11617	18	18		YD151-YD158, YL951-YR328
2002Z			AB		0-0	22-11-81	D45501J	S/R			D11617	S/R			YC064
2002Z			AB		0-0	22-11-81	D45501P	S/R			D11617	S/R			YC065-YD158, YL951-YR328
2003B	20	HF	AC		19-4	22-11-81	D45501J	6			D11617	21			YC064

WIRE LIST

D280A108

91-21-11

Section W7380

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7381	286A7381			AB1050L, AB1050R TO RUDDER POSN SENSOR, RUDDER ACTUATOR (continued)											
2003B	20	HF	AC		19-2	22-11-81	D45501P	6			D11617	21			YC065-YC070
2003B	20	HF	AC		17-11	22-11-81	D45501P	17			D11617	21			YD151-YD158
2003B	20	HF	AC		18-1	22-11-81	D45501P	17			D11617	21			YL951-YR328
2003R	20	HF	AC		0-0	22-11-81	D45501J	5			D11617	15			YC064
2003R	20	HF	AC		0-0	22-11-81	D45501P	5			D11617	15			YC065-YC070
2003R	20	HF	AC		0-0	22-11-81	D45501P	16			D11617	15			YD151-YD158, YL951-YR328
2003Z			AC		0-0	22-11-81	D45501J	S/R			D11617	S/R			YC064
2003Z			AC		0-0	22-11-81	D45501P	S/R			D11617	S/R			YC065-YD158, YL951-YR328
2004B	20	HF	AD		19-4	22-11-81	D45501J	8			D11617	24			YC064
2004B	20	HF	AD		19-2	22-11-81	D45501P	8			D11617	24			YC065-YC070
2004B	20	HF	AD		17-11	22-11-81	D45501P	19			D11617	24			YD151-YD158
2004B	20	HF	AD		18-1	22-11-81	D45501P	19			D11617	24			YL951-YR328
2004R	20	HF	AD		0-0	22-11-81	D45501J	7			D11617	11			YC064
2004R	20	HF	AD		0-0	22-11-81	D45501P	7			D11617	11			YC065-YC070
2004R	20	HF	AD		0-0	22-11-81	D45501P	18			D11617	11			YD151-YD158, YL951-YR328
2004Z			AD		0-0	22-11-81	D45501J	S/R			D11617	S/R			YC064
2004Z			AD		0-0	22-11-81	D45501P	S/R			D11617	S/R			YC065-YD158, YL951-YR328
2005B	20	HF	AE		19-0	22-11-81	D45501J	10			D11613	2			YC064
2005B	20	HF	AE		19-0	22-11-81	D45501P	10			D11613	2			YC065-YC070
2005B	20	HF	AE		17-8	22-11-81	D45501P	21			D11613	2			YD151-YD158, YL951-YR328
2005B	20	HF	AE		17-6	22-11-81	D45501P	21			D11613	2			YD157-YD158
2005R	20	HF	AE		0-0	22-11-81	D45501J	9			D11613	1			YC064
2005R	20	HF	AE		0-0	22-11-81	D45501P	9			D11613	1			YC065-YD158, YL951-YR328
2005Z			AE		0-0	22-11-81	D45501J	S/R			D11613	S/R			YC064
2005Z			AE		0-0	22-11-81	D45501P	S/R			D11613	S/R			YC065-YD158, YL951-YR328
2006B	20	HF	AF		21-8	22-11-81	D45503J	2			D11619	24			YC064
2006B	20	HF	AF		21-5	22-11-81	D45503P	2			D11619	24			YC065-YC070
2006R	20	HF	AF		0-0	22-11-81	D45503J	1			D11619	11			YC064
2006R	20	HF	AF		0-0	22-11-81	D45503P	1			D11619	11			YC065-YC070
2006Z			AF		0-0	22-11-81	D45503J	S/R			D11619	S/R			YC064
2006Z			AF		0-0	22-11-81	D45503P	S/R			D11619	S/R			YC065-YC070
2007B	20	HF	AG		21-8	22-11-81	D45503J	4			D11619	1			YC064

WIRE LIST

D280A108

91-21-11

Section W7380

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7381	286A7381			AB1050L, AB1050R TO RUDDER POSN SENSOR, RUDDER ACTUATOR (continued)											
2007B	20	HF	AG		21-5	22-11-81	D45503P		4		D11619		1		YC065-YC070
2007R	20	HF	AG		0-0	22-11-81	D45503J		3		D11619		6		YC064
2007R	20	HF	AG		0-0	22-11-81	D45503P		3		D11619		6		YC065-YC070
2007Z			AG		0-0	22-11-81	D45503J		S/R		D11619		S/R		YC064
2007Z			AG		0-0	22-11-81	D45503P		S/R		D11619		S/R		YC065-YC070
2008B	18	HF	AH		21-8	22-11-81	D45503J		6	18	D11619		13	18	YC064
2008B	18	HF	AH		21-5	22-11-81	D45503P		6	18	D11619		13	18	YC065-YC070
2008R	18	HF	AH		0-0	22-11-81	D45503J		5	18	D11619		18	18	YC064
2008R	18	HF	AH		0-0	22-11-81	D45503P		5	18	D11619		18	18	YC065-YC070
2008Z			AH		0-0	22-11-81	D45503J		S/R		D11619		S/R		YC064
2008Z			AH		0-0	22-11-81	D45503P		S/R		D11619		S/R		YC065-YC070
2009B	20	HF	AI		21-8	22-11-81	D45503J		8		D11619		21		YC064
2009B	20	HF	AI		21-5	22-11-81	D45503P		8		D11619		21		YC065-YC070
2009R	20	HF	AI		0-0	22-11-81	D45503J		7		D11619		15		YC064
2009R	20	HF	AI		0-0	22-11-81	D45503P		7		D11619		15		YC065-YC070
2009Z			AI		0-0	22-11-81	D45503J		S/R		D11619		S/R		YC064
2009Z			AI		0-0	22-11-81	D45503P		S/R		D11619		S/R		YC065-YC070
2010B	20	HF	AJ		21-5	22-11-81	D45503J		10		D11615		2		YC064
2010B	20	HF	AJ		21-4	22-11-81	D45503P		10		D11615		2		YC065-YC070
2010R	20	HF	AJ		0-0	22-11-81	D45503J		9		D11615		1		YC064
2010R	20	HF	AJ		0-0	22-11-81	D45503P		9		D11615		1		YC065-YC070
2010Z			AJ		0-0	22-11-81	D45503J		S/R		D11615		S/R		YC064
2010Z			AJ		0-0	22-11-81	D45503P		S/R		D11615		S/R		YC065-YC070
3001B	20	HG	CA		19-0	22-11-81	D45501J		12		D11613		4		YC064
3001B	20	HG	CA		19-0	22-11-81	D45501P		12		D11613		4		YC065-YC070
3001B	20	HG	CA		17-8	22-11-81	D45501P		23		D11613		4		YD151-YD158, YL951-YR328
3001B	20	HG	CA		17-6	22-11-81	D45501P		23		D11613		4		YD157-YD158
3001R	20	HG	CA		0-0	22-11-81	D45501J		11		D11613		3		YC064
3001R	20	HG	CA		0-0	22-11-81	D45501P		11		D11613		3		YC065-YC070
3001R	20	HG	CA		0-0	22-11-81	D45501P		22		D11613		3		YD151-YD158, YL951-YR328
3001Y	20	HG	CA		0-0	22-11-81	D45501J		13		D11613		5		YC064
3001Y	20	HG	CA		0-0	22-11-81	D45501P		13		D11613		5		YC065-YC070
3001Y	20	HG	CA		0-0	22-11-81	D45501P		24		D11613		5		YD151-YD158, YL951-YR328
3001Z			CA		0-0	22-11-81	D45501J		S/R		D11613		S/R		YC064
3001Z			CA		0-0	22-11-81	D45501P		S/R		D11613		S/R		YC065-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W7380

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To				Effectivity
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
W7381	286A7381			AB1050L, AB1050R TO RUDDER POSN SENSOR, RUDDER ACTUATOR (continued)											
3002B	20	HG	CB	21-5	22-11-81	D45503J	12				D11615	4		YC064	
3002B	20	HG	CB	21-4	22-11-81	D45503P	12				D11615	4		YC065-YC070	
3002R	20	HG	CB	0-0	22-11-81	D45503J	11				D11615	3		YC064	
3002R	20	HG	CB	0-0	22-11-81	D45503P	11				D11615	3		YC065-YC070	
3002Y	20	HG	CB	0-0	22-11-81	D45503J	13				D11615	5		YC064	
3002Y	20	HG	CB	0-0	22-11-81	D45503P	13				D11615	5		YC065-YC070	
3002Z			CB	0-0	22-11-81	D45503J	S/R				D11615	S/R		YC064	
3002Z			CB	0-0	22-11-81	D45503P	S/R				D11615	S/R		YC065-YC070	
W7383	286A7383			AB1050R TO RUDDER POSN SENSOR, RUDDER ACTUATOR											
1003	20	HE	C	6-0	22-11-81	D11619	14				GD00069	DC..	E	*	YD151-YD158, YL951-YR328
1003Z			C	0-0	22-11-81	D11619	S/R				GD00069	DC..	E	*	YD151-YD158, YL951-YR328
1004	20	HE	D	6-0	22-11-81	D11619	20				GD00069	DC..	E	*	YD151-YD158, YL951-YR328
1004Z			D	0-0	22-11-81	D11619	S/R				GD00069	DC..	E	*	YD151-YD158, YL951-YR328
2006B	20	HF	AF	19-6	22-11-81	D45503P	19				D11619	24			YD151-YD155, YL951-YR328
2006B	20	HF	AF	19-5	22-11-81	D45503P	19				D11619	24			YD157-YD158
2006R	20	HF	AF	0-0	22-11-81	D45503P	18				D11619	11			YD151-YD158, YL951-YR328
2006Z			AF	0-0	22-11-81	D45503P	S/R				D11619	S/R			YD151-YD158, YL951-YR328
2007B	20	HF	AG	19-6	22-11-81	D45503P	15				D11619	1			YD151-YD155, YL951-YR328
2007B	20	HF	AG	19-5	22-11-81	D45503P	15				D11619	1			YD157-YD158
2007R	20	HF	AG	0-0	22-11-81	D45503P	14				D11619	6			YD151-YD158, YL951-YR328
2007Z			AG	0-0	22-11-81	D45503P	S/R				D11619	S/R			YD151-YD158, YL951-YR328
2008B	18	HF	AH	19-6	22-11-81	D45503P	3	18			D11619	13	18		YD151-YD155, YL951-YR328
2008B	18	HF	AH	19-5	22-11-81	D45503P	3	18			D11619	13	18		YD157-YD158
2008R	18	HF	AH	0-0	22-11-81	D45503P	1	18			D11619	18	18		YD151-YD158, YL951-YR328
2008Z			AH	0-0	22-11-81	D45503P	S/R				D11619	S/R			YD151-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W7380

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7383	286A7383			AB1050R TO RUDDER POSN SENSOR, RUDDER ACTUATOR (continued)											
2009B	20	HF	AI		19-6	22-11-81	D45503P	17			D11619	21			YD151-YD155, YL951-YR328
2009B	20	HF	AI		19-5	22-11-81	D45503P	17			D11619	21			YD157-YD158
2009R	20	HF	AI		0-0	22-11-81	D45503P	16			D11619	15			YD151-YD158, YL951-YR328
2009Z				AI	0-0	22-11-81	D45503P	S/R			D11619	S/R			YD151-YD158, YL951-YR328
2010B	20	HF	AJ		19-1	22-11-81	D45503P	21			D11615	2			YD151-YD158
2010B	20	HF	AJ		19-2	22-11-81	D45503P	21			D11615	2			YL951-YR328
2010R	20	HF	AJ		0-0	22-11-81	D45503P	9			D11615	1			YD151-YD158, YL951-YR328
2010Z				AJ	0-0	22-11-81	D45503P	S/R			D11615	S/R			YD151-YD158, YL951-YR328
3002B	20	HG	CB		19-1	22-11-81	D45503P	23			D11615	4			YD151-YD158
3002B	20	HG	CB		19-2	22-11-81	D45503P	23			D11615	4			YL951-YR328
3002R	20	HG	CB		0-0	22-11-81	D45503P	22			D11615	3			YD151-YD158, YL951-YR328
3002Y	20	HG	CB		0-0	22-11-81	D45503P	24			D11615	5			YD151-YD158, YL951-YR328
3002Z				CB	0-0	22-11-81	D45503P	S/R			D11615	S/R			YD151-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W7380

Page 5 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

	Bundle No.	Part Number			Description			From				To				Effectivity
	Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	
I	W7500	286A7500			KEELBEAM OVERHEAT DETECTION											
I	1302R	20		H9	EN	1-7	26-12-11	D00850	= 1			D00852	= 1			ALL
I	1302Z				EN	0-0	26-12-11	D00850	DED			D00852	DED			ALL

For training purposes only!

WIRE LIST

D280A108

91-21-11

Section W7500

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From			To			Effectivity		
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term		Type	Splice
W7522	286A7522				FWD LEFT SIDE, WHEEL WELL AREA										
0501	18		HA		6-10	29-11-11	D46030P	10			D00762	A		YC051-YD152	
0501	18		HA		8-0	29-11-11	D46030P	10			D00762	A		YD153-YD158, YL951-YR323, YR325-YR328	
0502	18		HA		6-10	29-11-11	D46030P	2			D00762	B		YC051-YD152	
0502	18		HA		8-0	29-11-11	D46030P	2			D00762	B		YD153-YD158, YL951-YR323, YR325-YR328	
0503	18		HA		7-11	29-11-11	GD00330	DC..	E		D00762	E		YC051-YD152	
0503	18		HA		9-0	29-11-11	GD00330	DC..	E		D00762	E		YD153-YD158, YL951-YR323, YR325-YR328	
0504	20		HA		7-0	29-33-11	D46030P	11			D02684	3		YC051-YD152	
0504	20		HA		9-11	29-33-11	D46030P	11			D02684	3		YD153-YD158, YL951-YR323, YR325-YR328	
0505	20		HA		2-4	29-33-11	GD00330	DC..	E	*	D02684	2		YC051-YD152	
0505	20		HA		10-11	29-33-11	GD00330	DC..	E	*	D02684	2		YD153-YD158, YL951-YR323, YR325-YR328	
0506	20		HA		6-8	29-33-11	D46030P	9			D02680	2		YC051-YD152	
0506	20		HA		9-10	29-33-11	D46030P	9			D02680	2		YD153-YD158, YL951-YR323, YR325-YR328	
0507	20		HA		2-0	29-33-11	GD00330	DC..	E	*	D02680	3		YC051-YD152	
0507	20		HA		10-10	29-33-11	GD00330	DC..	E	*	D02680	3		YD153-YD158, YL951-YR323, YR325-YR328	
0508	18		HA		6-10	31-62-14	D00762		D		D46030P	1		YC051-YD152	
0508	18		HA		8-0	31-62-14	D00762		D		D46030P	1		YD153-YD158, YL951-YR323, YR325-YR328	
2601B	20		HF	SA	10-0	78-34-11	D46030P	17			D03052	2		YC051-YC055	
2601B	20		HF	SA	9-9	78-34-11	D46030P	17			D03052	2		YC056-YD152	
2601B	20		HF	SA	11-9	78-34-11	D46030P	17			D03052	2		YD153-YD158, YL951-YL963, YN231-YN235	

WIRE LIST

D280A108

91-21-11

Section W7520

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				Effectivity	
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W7522	286A7522				FWD LEFT SIDE, WHEEL WELL AREA (continued)											
2601B	20	HF	SA		11-8	78-34-11	D46030P	17			D03052	2			YL964-YL999, YN236-YR323, YR325-YR328	
2601R	20	HF	SA		0-0	78-34-11	D46030P	18			D03052	7			YC051-YD158, YL951-YR323, YR325-YR328	
2601Z			SA		0-0	78-34-11	D46030P	S/R			GD00760	ST..	E		YC051-YD158, YL951-YR323, YR325-YR328	
2602B	20	HF	SB		10-0	78-34-11	D46030P	19			D03052	4			YC051-YC055	
2602B	20	HF	SB		9-9	78-34-11	D46030P	19			D03052	4			YC056-YD152	
2602B	20	HF	SB		11-9	78-34-11	D46030P	19			D03052	4			YD153-YD158, YL951-YL963, YN231-YN235	
2602B	20	HF	SB		11-8	78-34-11	D46030P	19			D03052	4			YL964-YL999, YN236-YR323, YR325-YR328	
2602R	20	HF	SB		0-0	78-34-11	D46030P	7			D03052	5			YC051-YD158, YL951-YR323, YR325-YR328	
2602Z			SB		0-0	78-34-11	D46030P	S/R			GD00760	ST..	E		YC051-YD158, YL951-YR323, YR325-YR328	
2603B	20	HF	SC		10-0	78-34-11	D46030P	3			D03052	6			YC051-YC055	
2603B	20	HF	SC		9-9	78-34-11	D46030P	3			D03052	6			YC056-YD152	
2603B	20	HF	SC		11-9	78-34-11	D46030P	3			D03052	6			YD153-YD158, YL951-YL963, YN231-YN235	
2603B	20	HF	SC		11-8	78-34-11	D46030P	3			D03052	6			YL964-YL999, YN236-YR323, YR325-YR328	
2603R	20	HF	SC		0-0	78-34-11	D46030P	4			D03052	3			YC051-YD158, YL951-YR323, YR325-YR328	
2603Z			SC		0-0	78-34-11	D46030P	S/R			GD00760	ST..	E		YC051-YD158, YL951-YR323, YR325-YR328	
3601B	20	HG	A4		10-2	78-36-11	D46030P	12			D03054	4			YC051-YC055	
3601B	20	HG	A4		9-7	78-36-11	D46030P	12			D03054	4			YC056-YD152	

WIRE LIST

D280A108

91-21-11

Section W7520

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7522	286A7522				FWD LEFT SIDE, WHEEL WELL AREA (continued)										
3601B	20	HG	A4		11-7	78-36-11	D46030P	12			D03054	4			YD153-YD157, YL964-YL999, YN236-YR323, YR325-YR328
3601B	20	HG	A4		11-8	78-36-11	D46030P	12			D03054	4			YD158, YL951-YL963, YN231-YN235
3601R	20	HG	A4		0-0	78-36-11	D46030P	14			D03054	2			YC051-YD158, YL951-YR323, YR325-YR328
3601Y	20	HG	A4		0-0	78-36-11	D46030P	13			D03054	3			YC051-YD158, YL951-YR323, YR325-YR328
3601Z				A4	0-0	78-36-11	D46030P	S/R			GD00760	ST..	E	*	YC051-YD158, YL951-YR323, YR325-YR328
3602B	20	HG	B4		10-2	78-36-11	D46030P	6			D03054	7			YC051-YC055
3602B	20	HG	B4		9-7	78-36-11	D46030P	6			D03054	7			YC056-YD152
3602B	20	HG	B4		11-7	78-36-11	D46030P	6			D03054	7			YD153-YD157, YL964-YL999, YN236-YR323, YR325-YR328
3602B	20	HG	B4		11-8	78-36-11	D46030P	6			D03054	7			YD158, YL951-YL963, YN231-YN235
3602R	20	HG	B4		0-0	78-36-11	D46030P	15			D03054	5			YC051-YD158, YL951-YR323, YR325-YR328
3602Y	20	HG	B4		0-0	78-36-11	D46030P	16			D03054	6			YC051-YD158, YL951-YR323, YR325-YR328
3602Z				B4	0-0	78-36-11	D46030P	S/R			GD00760	ST..	E	*	YC051-YD158, YL951-YR323, YR325-YR328
6001R	18	9P			3-10	26-12-11	D46030P	8			D00840	= 1			YC051-YC054
6001R	18	9P			3-9	26-12-11	D46030P	8			D00840	= 1			YC055
6001R	18	9P			3-8	26-12-11	D46030P	8			D00840	= 1			YC056-YD152
6001R	18	9P			5-1	26-12-11	D46030P	8			D00840	= 1			YD153-YD157
6001R	18	9P			5-3	26-12-11	D46030P	8			D00840	= 1			YD158
6001R	18	9P			5-2	26-12-11	D46030P	8			M00270	= A	N		YL951-YR323, YR325-YR328

WIRE LIST

D280A108

91-21-11

Section W7520

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	Wire No.	GA	CO TY		Equip	Term		Type	Splice	Equip	Term	Type	Splice			
W7526	286A7526				AFT LEFT SIDE WHEEL WELL AREA											
0501	20		HA		7-7	29-31-11	D46032P		1			D00674	1			YC051-YD152
0501	20		HA		7-6	29-31-11	D46032P		1			D00674	1			YD153-YD158
0502	20		HA		7-7	29-31-11	D46032P		2			D00674	2			YC051-YD152
0502	20		HA		7-6	29-31-11	D46032P		2			D00674	2			YD153-YD158
0503	20		HA		7-7	29-31-11	D46032P		3			D00674	3			YC051-YD152
0503	20		HA		7-6	29-31-11	D46032P		3			D00674	3			YD153-YD158
0510	20		HA		4-7	29-31-11	GD00304		ST..	E		D00674	5			YC051-YD152
0510	20		HA		5-1	29-31-11	GD00304		ST..	E		D00674	5			YD153-YD158
0511	18		HA		3-9	32-44-11	D46032P		8			D00928	3			YC051-YD152
0511	18		HA		3-10	32-44-11	D46032P		8			D00928	3			YD153
0511	18		HA		3-11	32-44-11	D46032P		8			D00928	3			YD154-YD158
0512	18		HA		3-5	32-44-11	GD00308		DC..	E		D00928	1			YC051-YD152
0512	18		HA		3-1	32-44-11	GD00308		DC..	E		D00928	1			YD153
0512	18		HA		3-2	32-44-11	GD00308		DC..	E		D00928	1			YD154-YD158
0513	18		HA		3-9	32-44-11	D46032P		7			D00928	2			YC051-YD152
0513	18		HA		3-10	32-44-11	D46032P		7			D00928	2			YD153
0513	18		HA		3-11	32-44-11	D46032P		7			D00928	2			YD154-YD158
0514	18		HA		3-9	32-44-11	D46032P		10			D00928	8			YC051-YD152
0514	18		HA		3-10	32-44-11	D46032P		10			D00928	8			YD153
0514	18		HA		3-11	32-44-11	D46032P		10			D00928	8			YD154-YD158
0515	18		HA		3-5	32-44-11	GD00308		DC..	E		D00928	9			YC051-YD152
0515	18		HA		3-1	32-44-11	GD00308		DC..	E		D00928	9			YD153
0515	18		HA		3-2	32-44-11	GD00308		DC..	E		D00928	9			YD154-YD158
0516	18		HA		3-9	32-44-11	D46032P		11			D00928	10			YC051-YD152
0516	18		HA		3-10	32-44-11	D46032P		11			D00928	10			YD153
0516	18		HA		3-11	32-44-11	D46032P		11			D00928	10			YD154-YD158
0517	18		HA		3-9	32-44-11	D46032P		9			D00928	4			YC051-YD152
0517	18		HA		3-10	32-44-11	D46032P		9			D00928	4			YD153
0517	18		HA		3-11	32-44-11	D46032P		9			D00928	4			YD154-YD158
0518	18		HA		6-5	27-23-11	D46032P		12			D00822	2			YC051-YD152
0518	18		HA		7-1	27-23-11	D46032P		12			D00822	2			YD153
0518	18		HA		7-0	27-23-11	D46032P		12			D00822	2			YD154-YD157
0518	18		CQ		7-0	27-23-11	D46032P		12			D00822	2			YD158
0519	18		HA		6-5	27-23-11	D46032P		13			D00822	3			YC051-YD152
0519	18		HA		7-1	27-23-11	D46032P		13			D00822	3			YD153
0519	18		HA		7-0	27-23-11	D46032P		13			D00822	3			YD154-YD157
0519	18		CQ		7-0	27-23-11	D46032P		13			D00822	3			YD158
0520	18		HA		6-5	27-23-14	D46032P		14			D00822	4			YC051-YD152
0520	18		HA		7-1	27-23-14	D46032P		14			D00822	4			YD153

WIRE LIST

D280A108

91-21-11

Section W7520

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7526	286A7526			AFT LEFT SIDE WHEEL WELL AREA (continued)											
0520	18		HA		7-0	27-23-14	D46032P		14		D00822		4		YD154-YD157
0520	18		CQ		7-0	27-23-14	D46032P		14		D00822		4		YD158
0521	18		HA		2-3	27-23-11	GD00316	DC..	E		D00822		1		YC051-YD152
0521	18		HA		2-9	27-23-11	GD00316	DC..	E		D00822		1		YD153
0521	18		HA		3-6	27-23-11	GD00316	DC..	E		D00822		1		YD154-YD157
0521	18		CQ		3-6	27-23-11	GD00316	DC..	E		D00822		1		YD158
2201B	18		HF	KA	3-9	32-41-11	D46032P		5		D00926		2		YC051-YD152
2201B	18		HF	KA	4-0	32-41-11	D46032P		5		D00926		2		YD153-YD158
2201R	18		HF	KA	0-0	32-41-11	D46032P		4		D00926		1		YC051-YD158
2201Z				KA	0-0	32-41-11	D46032P		S/R		D00926		S/R		YC051-YD158
6001R	20		9P		9-2	26-12-11	D46032P		6		D00854		=1		YC051-YD152
6001R	20		9P		9-4	26-12-11	D46032P		6		D00854		=1		YD153
6001R	20		9P		9-3	26-12-11	D46032P		6		D00854		=1		YD154-YD158

WIRE LIST
D280A108

91-21-11
Section W7520
Page 5 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

	Bundle No.	Part Number			Description			From				To				
	Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I	W7538	286A7538			APU FIRE DETECTION AND LIGHTING											
	0002	18		HA		3-11	33-35-11	D40060P		5		S00086	1	G7		YC051-YD151
I	0002	18		HA		4-2	33-35-11	D40060P		5		S00086	3	G7		YD152-YR328
	0004	18		HA		4-3	33-35-11	D40060P		6		L00205	B	G7		YC051-YD151
I	0004	18		HA		4-5	33-35-11	D40060P		6		L00205	B	G7		YD152-YR328
I	0005	18		HA		1-5	33-35-11	L00205	A	G7		S00086	2	G7	*	ALL
	0006	18		HA		6-0	33-35-11	D40060P		7		L01308	B	G7		YC051-YD151
I	0006	18		HA		6-2	33-35-11	D40060P		7		L01308	B	G7		YD152-YR328
I	0007	18		HA		7-11	33-35-11	L01308	A	G7		S00086	2	G7	*	ALL
I	6001R	18		9P		9-7	26-11-31	D40062J		1		M01755	T/1	GW	*	ALL
	6002R	18		9P		7-5	26-11-31	D40060P		3		D40062J	3			YC051-YD151
I	6002R	18		9P		7-7	26-11-31	D40060P		3		D40062J	3			YD152-YR328
	6003R	18		9P		4-0	26-11-31	D40060P		2		M01755	T/1	GW	*	YC051-YD151
I	6003R	18		9P		4-2	26-11-31	D40060P		2		M01755	T/1	GW	*	YD152-YR328
	6004R	18		9P		3-7	26-11-31	D40060P		10		M01755	GND	GY		YC051-YD151
I	6004R	18		9P		3-9	26-11-31	D40060P		10		M01755	GND	GY		YD152-YR328
	6005R	18		9P		7-5	26-11-31	D40060P		9		D40062J	5			YC051-YD151
I	6005R	18		9P		7-7	26-11-31	D40060P		9		D40062J	5			YD152-YR328

WIRE LIST

D280A108

91-21-11

Section W7530

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To			
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice Effectivity
I W7540	286A7540				APU FIRE DETECTION									
I 6001R	18		9P		4-0	26-11-31	D40062P		1		M01756	T/1	GW	ALL
I 6002R	18		9P		3-7	26-11-31	D40062P		3		M01756	GND	GY	ALL

For training purposes only!

WIRE LIST
D280A108

91-21-11
Section W7540
Page 1 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7580	286A7580			WHEEL WELL DISC STS 675L TO CENTER TANK DISC M1830											
1301	20	C2	EN		5-4	28-41-11	D04850P	32			D11316	1			YC051-YC055
1301	20	C2	EN		5-3	28-41-11	D04850P	32			D11316	1			YC056-YD152
1301	20	C2	EN		8-9	28-41-11	D04850P	32			D11316	1			YD153-YD158, YL951-YR328
1301ZI			EN		0-0	28-41-11	D04850P			FA	D11316	= C1			YC051-YD158, YL951-YR328
1301ZO			EN		0-0	28-41-11	D04850P		S/R		GD03774	ST..	E		YC051-YD158, YL951-YR328
1302	20	C1	EP		5-4	28-41-11	D04850P	36			D11316	3			YC051-YC055
1302	20	C1	EP		5-3	28-41-11	D04850P	36			D11316	3			YC056-YD152
1302	20	C1	EP		8-9	28-41-11	D04850P	36			D11316	3			YD153-YD158, YL951-YR328
1302Z			EP		0-0	28-41-11	D04850P		S/R		GD03774	ST..	E		YC051-YD158, YL951-YR328
1303	20	C1	EQ		5-4	28-41-11	D04850P	19			D11316	2			YC051-YC055
1303	20	C1	EQ		5-3	28-41-11	D04850P	19			D11316	2			YC056-YD152
1303	20	C1	EQ		8-9	28-41-11	D04850P	19			D11316	2			YD153-YD158, YL951-YR328
1303Z			EQ		0-0	28-41-11	D04850P		S/R		GD03774	ST..	E		YC051-YD158, YL951-YR328
6001	20	HA			0-7	28-41-11	D04850P	16			D04850P	15			YC051-YD158, YL951-YR328
6002	20	HA			0-7	28-41-11	D04850P	50			D04850P	51			YC051-YD158, YL951-YR328
FRAA					0-0	28-41-11	D04850P	31	18		D04850P			FA	YC051-YD158, YL951-YR328
FRAB					0-0	28-41-11	D04850P	33	18		D04850P			FA	YC051-YD158, YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W7580

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W7592	286A7592	P8 (FIRE SW PNL) TO FIRE EXTINGUISHER BOTTLES+VALVES,SYSTEM NO 1													
6001R	20 QZ		59-4	26-21-11	D40656P	A03			D40010P	1			YC051-YC055		
6001R	20 QZ		59-5	26-21-11	D40656P	A03			D40010P	1			YC056-YL999, YR301-YR328		
6001R	20 QZ		49-0	26-21-11	D40656P	A03			D40010P	1			YN231-YN501		
6002R	20 QZ		59-4	26-21-11	D40656P	B01			D40010P	2			YC051-YC055		
6002R	20 QZ		59-5	26-21-11	D40656P	B01			D40010P	2			YC056-YL999, YR301-YR328		
6002R	20 QZ		49-0	26-21-11	D40656P	B01			D40010P	2			YN231-YN501		
6003R	20 QZ		59-4	26-21-11	D40656P	A02			D40010P	3			YC051-YC055		
6003R	20 QZ		59-5	26-21-11	D40656P	A02			D40010P	3			YC056-YL999, YR301-YR328		
6003R	20 QZ		49-0	26-21-11	D40656P	A02			D40010P	3			YN231-YN501		
6004R	20 QZ		60-1	26-21-11	D40656P	A01			D40652P	6			YC051-YL954		
6004R	20 QZ		60-2	26-21-11	D40656P	A01			D40652P	6			YL955-YL999, YR301-YR328		
6004R	20 QZ		49-8	26-21-11	D40656P	A01			D40652P	6			YN231-YN501		
6006R	20 QZ		60-1	26-21-11	D40656P	B02			D40652P	8			YC051-YL954		
6006R	20 QZ		60-2	26-21-11	D40656P	B02			D40652P	8			YL955-YL999, YR301-YR328		
6006R	20 QZ		49-8	26-21-11	D40656P	B02			D40652P	8			YN231-YN501		
6007R	20 QZ		2-1	26-21-11	D40010P	4			D40652P	9			ALL		
6008R	20 QZ		60-1	26-21-11	D40656P	B03			D40652P	10			YC051-YL954		
6008R	20 QZ		60-2	26-21-11	D40656P	B03			D40652P	10			YL955-YL999, YR301-YR328		
6008R	20 QZ		49-8	26-21-11	D40656P	B03			D40652P	10			YN231-YN501		
6009R	20 QZ		2-1	26-21-11	D40010P	5			D40652P	11			ALL		
6010R	20 QZ		2-3	26-21-11	D40652P	1			GD00342	DC..	E	*1	ALL		
6011R	20 QZ		2-3	26-21-11	D40652P	2			GD00342	DC..	E	*1	ALL		
6012R	20 QZ		2-3	26-21-11	D40652P	3			GD00342	DC..	E	*2	ALL		
6013R	20 QZ		2-3	26-21-11	D40652P	4			GD00342	DC..	E	*2	ALL		
6014R	20 QZ		2-3	26-21-11	D40652P	5			GD00342	DC..	E	*2	ALL		
W7594	286A7594	P8(FIRE SW PNL AREA) TO FIRE EXT BOTTLE SYSTEM NO.2													
6001R	20 QZ		67-11	26-21-11	D40012P	B02			D40010J	5			YC051-YC055		
6001R	20 QZ		68-1	26-21-11	D40012P	B02			D40010J	5			YC056-YL954		
6001R	20 QZ		68-3	26-21-11	D40012P	B02			D40010J	5			YL955-YL999, YR301-YR328		
6001R	20 QZ		58-0	26-21-11	D40012P	B02			D40010J	5			YN231-YN235		
6001R	20 QZ		58-3	26-21-11	D40012P	B02			D40010J	5			YN236-YN501		

WIRE LIST

D280A108

91-21-11
Section W7590
Page 1
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W7594	286A7594			P8(FIRE SW PNL AREA) TO FIRE EXT BOTTLE SYSTEM NO.2 (continued)											
6002R	20		QZ		67-11	26-21-11	D40012P	B01			D40010J	4			YC051-YC055
6002R	20		QZ		68-1	26-21-11	D40012P	B01			D40010J	4			YC056-YL954
6002R	20		QZ		68-3	26-21-11	D40012P	B01			D40010J	4			YL955-YL999, YR301-YR328
6002R	20		QZ		58-0	26-21-11	D40012P	B01			D40010J	4			YN231-YN235
6002R	20		QZ		58-3	26-21-11	D40012P	B01			D40010J	4			YN236-YN501
6003R	20		QZ		67-6	26-21-11	D40012P	A01			D40008P	6			YC051-YC055
6003R	20		QZ		67-7	26-21-11	D40012P	A01			D40008P	6			YC056-YD152
6003R	20		QZ		67-9	26-21-11	D40012P	A01			D40008P	6			YD153-YL999, YR301-YR328
6003R	20		QZ		57-7	26-21-11	D40012P	A01			D40008P	6			YN231-YN235
6003R	20		QZ		57-9	26-21-11	D40012P	A01			D40008P	6			YN236-YN501
6004R	20		QZ		67-6	26-21-11	D40012P	A02			D40008P	4			YC051-YC055
6004R	20		QZ		67-7	26-21-11	D40012P	A02			D40008P	4			YC056-YD152
6004R	20		QZ		67-9	26-21-11	D40012P	A02			D40008P	4			YD153-YL999, YR301-YR328
6004R	20		QZ		57-7	26-21-11	D40012P	A02			D40008P	4			YN231-YN235
6004R	20		QZ		57-9	26-21-11	D40012P	A02			D40008P	4			YN236-YN501
6005R	20		QZ		2-7	26-21-11	D40008P		1		D40010J	1			YC051-YD152, YL955-YL999, YN236-YR328
6005R	20		QZ		2-8	26-21-11	D40008P		1		D40010J	1			YD153-YL954, YN231-YN235
6007R	20		QZ		2-7	26-21-11	D40008P		3		D40010J	2			YC051-YD152, YL955-YL999, YN236-YR328
6007R	20		QZ		2-8	26-21-11	D40008P		3		D40010J	2			YD153-YL954, YN231-YN235
6008R	20		QZ		2-7	26-21-11	D40008P		5		D40010J	3			YC051-YD152, YL955-YL999, YN236-YR328
6008R	20		QZ		2-8	26-21-11	D40008P		5		D40010J	3			YD153-YL954, YN231-YN235
6009R	20		QZ		2-3	26-21-11	D40008P		7		GD00344	DC..	E	*1	YC051-YD152, YL955-YL999, YN236-YR328
6009R	20		QZ		2-4	26-21-11	D40008P		7		GD00344	DC..	E	*1	YD153-YL954, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W7590

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number GA CO TY			Fam	Description FT-IN Diagram		From Equip	Term	Type	Splice	To Equip	Term	Type	Splice	Effectivity
W7594	286A7594				P8(FIRE SW PNL AREA) TO FIRE EXT BOTTLE SYSTEM NO.2 (continued)										
6010R	20	QZ			2-3	26-21-11	D40008P	8			GD00344	DC..	E	*1	YC051-YD152, YL955-YL999, YN236-YR328
6010R	20	QZ			2-4	26-21-11	D40008P	8			GD00344	DC..	E	*1	YD153-YL954, YN231-YN235
6011R	20	QZ			2-3	26-21-11	D40008P	9			GD00344	DC..	E	*2	YC051-YD152, YL955-YL999, YN236-YR328
6011R	20	QZ			2-4	26-21-11	D40008P	9			GD00344	DC..	E	*2	YD153-YL954, YN231-YN235
6012R	20	QZ			2-3	26-21-11	D40008P	10			GD00344	DC..	E	*2	YC051-YD152, YL955-YL999, YN236-YR328
6012R	20	QZ			2-4	26-21-11	D40008P	10			GD00344	DC..	E	*2	YD153-YL954, YN231-YN235
6013R	20	QZ			2-3	26-21-11	D40008P	11			GD00344	DC..	E	*2	YC051-YD152, YL955-YL999, YN236-YR328
6013R	20	QZ			2-4	26-21-11	D40008P	11			GD00344	DC..	E	*2	YD153-YL954, YN231-YN235
W7596	286A7596				JUMPER BUNDLE-LEFT BOTTLE										
6001R	20	QZ			2-3	26-21-11	D40652J	3			D00582		7		YC051-YD152
6001R	20	QZ			2-2	26-21-11	D40652J	3			D00582		7		YD153-YD158, YL951-YR328
6002R	20	QZ			2-3	26-21-11	D40652J	2			D00582		3		YC051-YD152
6002R	20	QZ			2-2	26-21-11	D40652J	2			D00582		3		YD153-YD158, YL951-YR328
6003R	20	QZ			2-3	26-21-11	D40652J	9			D00582		6		YC051-YD152
6003R	20	QZ			2-2	26-21-11	D40652J	9			D00582		6		YD153-YD158, YL951-YR328
6004R	20	QZ			2-5	26-21-11	D40652J	11			D01322		6		YC051-YD158, YL951-YR328
6005R	20	QZ			2-3	26-21-11	D40652J	6			D00586		2		YC051-YD152
6005R	20	QZ			2-1	26-21-11	D40652J	6			D00586		2		YD153-YD158, YL951-YR328
6007R	20	QZ			2-5	26-21-11	D40652J	10			D01322		4		YC051-YD158, YL951-YR328
6008R	20	QZ			2-3	26-21-11	D40652J	8			D00582		4		YC051-YD152

WIRE LIST

D280A108

91-21-11

Section W7590

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To				Effectivity	
	GA	CO	TY		FT-IN	Equip		Term	Type	Splice	Equip	Term	Type	Splice		
W7596	286A7596				JUMPER BUNDLE-LEFT BOTTLE (continued)											
6008R	20		QZ		2-2	26-21-11	D40652J		8			D00582	4		YD153-YD158, YL951-YR328	
6009R	20		QZ		2-5	26-21-11	D40652J		5			D01322	7		YC051-YD158, YL951-YR328	
6010R	20		QZ		2-5	26-21-11	D40652J		4			D01322	3		YC051-YD158, YL951-YR328	
6011R	20		QZ		2-3	26-21-11	D40652J		1			D00586	1		YC051-YD152	
6011R	20		QZ		2-1	26-21-11	D40652J		1			D00586	1		YD153-YD158, YL951-YR328	
W7598	286A7598				JUMPER BUNDLE-RIGHT BOTTLE											
6001R	20		QZ		2-1	26-21-11	D40008J		11			D00584	7		YC051-YD158, YL951-YR328	
6002R	20		QZ		2-1	26-21-11	D40008J		10			D00584	3		YC051-YD158, YL951-YR328	
6003R	20		QZ		2-1	26-21-11	D40008J		6			D00584	6		YC051-YD158, YL951-YR328	
6004R	20		QZ		2-3	26-21-11	D40008J		4			D01324	6		YC051-YD158, YL951-YR328	
6005R	20		QZ		2-3	26-21-11	D40008J		1			D00588	2		YC051-YD158, YL951-YR328	
6007R	20		QZ		2-3	26-21-11	D40008J		3			D01324	4		YC051-YD158, YL951-YR328	
6008R	20		QZ		2-1	26-21-11	D40008J		5			D00584	4		YC051-YD158, YL951-YR328	
6009R	20		QZ		2-3	26-21-11	D40008J		9			D01324	7		YC051-YD158, YL951-YR328	
6010R	20		QZ		2-3	26-21-11	D40008J		8			D01324	3		YC051-YD158, YL951-YR328	
6011R	20		QZ		2-3	26-21-11	D40008J		7			D00588	1		YC051-YD158, YL951-YR328	

WIRE LIST

D280A108

91-21-11

Section W7590

Page 4 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I	W7761	286A7761			HF-1 COUPLER ANT FEED										
I	001CO			AA	0-0	23-11-11	D00337		= C1		D04217P		= C1		ALL
I	001CX		0G	AA	7-3	23-11-11	D00337		= A1		D04217P		= A1		YC051-YD157
	001CX		0G	AA	7-5	23-11-11	D00337		= A1		D04217P		= A1		YD158-YL955, YN231-YN235
	001CX		0G	AA	7-6	23-11-11	D00337		= A1		D04217P		= A1		YL956-YL999, YN236-YR328
I	W7763	286A7763			HF-1 COUPLER ANT FEED										
I	001CO			AA	0-0	23-11-21	D00625		= C1		D04713P		= C1		YD158-YR328
	001CX		0G	AA	7-8	23-11-21	D00625		= A1		D04713P		= A1		YD158-YL955, YN231-YN235
	001CX		0G	AA	7-7	23-11-21	D00625		= A1		D04713P		= A1		YL956-YL999, YN236-YR328

WIRE LIST
D280A108

91-21-11
Section W7760
Page 1 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I W8022	286A8022			#1 RIGHT GEAR DOWN AND LOCKED SENSOR											
I A-B				0-0	32-64-11	D46012P			2		S00073		BLU		ALL
I A-R				0-0	32-64-11	D46012P			1		S00073		RED		ALL
I A-Y				0-0	32-64-11	D46012P			3		S00073		YEL		ALL
I W8024	286A8024			#2 RIGHT GEAR DOWN AND LOCKED SENSOR											
I A-B				0-0	32-64-12	D46018P			2		S00301		BLU		ALL
I A-R				0-0	32-64-12	D46018P			1		S00301		RED		ALL
I A-Y				0-0	32-64-12	D46018P			3		S00301		YEL		ALL

WIRE LIST

D280A108

91-21-11

Section W8020

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W8030	286A8030				AB1030C DISC (STA 1038) TO RIGHT AND LEFT ELEV DISC (W/O FLAT BLKHD)										
0501	18		HL		8-11	33-49-11	D40190P	10			SM00001		9		YC051-YC055
0501	18		HL		7-9	33-49-11	D40190P	10			SM00001		9		YC056-YD153, YD158-YR328
0501	18		HL		7-11	33-49-11	D40190P	10			SM00001		9		YD154-YD157
0502	18		HL		15-1	33-49-11	D40190P	7			GD00060	AC..	1		YC051-YC052
0502	18		HL		13-10	33-49-11	D40190P	7			GD00060	AC..	1		YC053-YC055
0502	18		HL		13-11	33-49-11	D40190P	7			GD00060	AC..	1		YC056-YD153
0502	18		HL		14-0	33-49-11	D40190P	7			GD00036	AC..	1		YD154-YL952, YN231-YN234
0502	18		HL		14-1	33-49-11	D40190P	7			GD00036	AC..	1		YL953-YL999, YN235-YR328
0503	18		HL		15-1	33-49-11	D40190P	4			GD00060	ST..	1		YC051-YC052
0503	18		HL		13-10	33-49-11	D40190P	4			GD00060	ST..	1		YC053-YC055
0503	18		HL		13-11	33-49-11	D40190P	4			GD00060	ST..	1		YC056-YD153
0503	18		HL		14-0	33-49-11	D40190P	4			GD00036	ST..	1		YD154-YL952, YN231-YN234
0503	18		HL		14-1	33-49-11	D40190P	4			GD00036	ST..	1		YL953-YL999, YN235-YR328
0511	18		HL		1-0	33-49-11	D40188P	10			SM00001		9		YC051-YD153, YD158-YR328
0511	18		HL		0-11	33-49-11	D40188P	10			SM00001		9		YD154-YD157
0512	18		HL		12-10	33-49-11	D40188P	7			GD00060	AC..	1		YC051-YC052
0512	18		HL		11-8	33-49-11	D40188P	7			GD00060	AC..	1		YC053-YD153
0512	18		HL		11-9	33-49-11	D40188P	7			GD00036	AC..	1		YD154-YL952, YN231-YN234
0512	18		HL		11-10	33-49-11	D40188P	7			GD00036	AC..	1		YL953-YL999, YN235-YR328
0513	18		HL		12-10	33-49-11	D40188P	4			GD00060	ST..	1		YC051-YC052
0513	18		HL		11-8	33-49-11	D40188P	4			GD00060	ST..	1		YC053-YD153
0513	18		HL		11-9	33-49-11	D40188P	4			GD00036	ST..	1		YD154-YL952, YN231-YN234
0513	18		HL		11-10	33-49-11	D40188P	4			GD00036	ST..	1		YL953-YL999, YN235-YR328
0521	18		HL		15-6	33-49-11	SM00001		9		D40192P	6	18		YC051-YC052
0521	18		HL		16-5	33-49-11	SM00001		9		D40192P	6	18		YC053-YC055, YD154-YD157
0521	18		HL		16-4	33-49-11	SM00001		9		D40192P	6	18		YC056-YD153, YD158-YR328
0522	18		HL		17-4	27-31-11	D10529		1		D40192P	7	18		YC051-YC052

WIRE LIST

D280A108

91-21-11

Section W8030

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W8030		286A8030			AB1030C DISC (STA 1038) TO RIGHT AND LEFT ELEV DISC (W/O FLAT BLKHD) (continued)											
0522		18		HL		18-0	27-31-11	D10529		1		D40192P	7	18		YC053-YC055, YC065-YL999, YN235-YR328
0522		18		HL		17-9	27-31-11	D10529		1		D40192P	7	18		YC056-YC064, YN231-YN234
0523		18		HL		14-3	27-31-11	D10529		2		GD00060	DC..	1		YC051-YC052
0523		18		HL		12-9	27-31-11	D10529		2		GD00060	DC..	1		YC053-YC055
0523		18		HL		12-7	27-31-11	D10529		2		GD00060	DC..	1		YC056-YC064
0523		18		HL		12-10	27-31-11	D10529		2		GD00060	DC..	1		YC065-YD153
0523		18		HL		12-10	27-31-11	D10529		2		GD00036	DC..	1		YD154-YL952
0523		18		HL		13-0	27-31-11	D10529		2		GD00036	DC..	1		YL953-YL999, YN235-YR328
0523		18		HL		12-8	27-31-11	D10529		2		GD00036	DC..	1		YN231-YN234
0524		18		HL		17-8	27-31-11	D10531		1		D40192P	24	18		YC051-YC052
0524		18		HL		18-5	27-31-11	D10531		1		D40192P	24	18		YC053-YC055
0525		18		HL		14-7	27-31-11	D10531		2		GD00060	DC..	1		YC051-YC052
0525		18		HL		13-2	27-31-11	D10531		2		GD00060	DC..	1		YC053-YC055
2201B		20		HQ	KA	18-2	27-38-11	D40190P		1		D40192P		1		YC051-YC052
2201B		20		HQ	KA	19-1	27-38-11	D40190P		1		D40192P		1		YC053-YR328
2201R		20		HQ	KA	0-0	27-38-11	D40190P		2		D40192P		2		ALL
2201Z					KA	0-0	27-38-11	D40190P		S/R		D40192P		S/R		ALL
2211B		20		HQ	KB	15-11	27-38-11	D40188P		1		D40192P		11		YC051-YC052
2211B		20		HQ	KB	16-11	27-38-11	D40188P		1		D40192P		11		YC053-YC055
2211B		20		HQ	KB	16-10	27-38-11	D40188P		1		D40192P		11		YC056-YR328
2211R		20		HQ	KB	0-0	27-38-11	D40188P		2		D40192P		12		ALL
2211Z					KB	0-0	27-38-11	D40188P		S/R		D40192P		S/R		ALL
2231B		20		HQ	KC	17-10	27-48-11	D01249		1		D40192P		16		YC051-YC052
2231B		20		HQ	KC	18-10	27-48-11	D01249		1		D40192P		16		YC053-YC055
2231B		20		HQ	KC	18-9	27-48-11	D01249		1		D40192P		16		YC056-YD157
2231B		20		HQ	KC	17-4	27-48-11	D01249		1		D40192P		16		YD158-YR328
2231R		20		HQ	KC	0-0	27-48-11	D01249		2		D40192P		17		ALL
2231Z					KC	0-0	27-48-11	D01249		S/R		D40192P		S/R		ALL
3201B		20		HR	YA	18-2	27-38-11	D40190P		5		D40192P		5		YC051-YC052
3201B		20		HR	YA	19-1	27-38-11	D40190P		5		D40192P		5		YC053-YR328
3201R		20		HR	YA	0-0	27-38-11	D40190P		6		D40192P		4		ALL
3201Y		20		HR	YA	0-0	27-38-11	D40190P		3		D40192P		3		ALL
3201Z					YA	0-0	27-38-11	D40190P		S/R		D40192P		S/R		ALL
3211B		20		HR	YB	15-11	27-38-11	D40188P		5		D40192P		15		YC051-YC052
3211B		20		HR	YB	16-11	27-38-11	D40188P		5		D40192P		15		YC053-YC055

WIRE LIST

D280A108

91-21-11

Section W8030

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W8030	286A8030				AB1030C DISC (STA 1038) TO RIGHT AND LEFT ELEV DISC (W/O FLAT BLKHD) (continued)										
3211B	20	HR	YB		16-10	27-38-11	D40188P		5		D40192P	15			YC056-YR328
3211R	20	HR	YB		0-0	27-38-11	D40188P		6		D40192P	14			ALL
3211Y	20	HR	YB		0-0	27-38-11	D40188P		3		D40192P	13			ALL
3211Z			YB		0-0	27-38-11	D40188P		S/R		D40192P	S/R			ALL
3231B	20	HR	YC		17-10	27-48-11	D01249		5		D40192P	20			YC051-YC052
3231B	20	HR	YC		18-10	27-48-11	D01249		5		D40192P	20			YC053-YC055
3231B	20	HR	YC		18-9	27-48-11	D01249		5		D40192P	20			YC056-YD157
3231B	20	HR	YC		17-4	27-48-11	D01249		5		D40192P	20			YD158-YR328
3231R	20	HR	YC		0-0	27-48-11	D01249		4		D40192P	19			ALL
3231Y	20	HR	YC		0-0	27-48-11	D01249		3		D40192P	18			ALL
3231Z			YC		0-0	27-48-11	D01249		S/R		D40192P	S/R			ALL
W8032	286A8032				#2 NOSE GEAR ON GROUND SENSOR										
A-B					0-0	32-31-12	TB0040K	C003	1		S01015	BLU			ALL
A-R					0-0	32-31-12	TB0040K	A003	1		S01015	RED			ALL
A-Y					0-0	32-31-12	TB0040K	E003	1		S01015	YEL			ALL
W8034	286A8034				#2 NOSE GEAR LOCKED SENSOR										
A-B					0-0	32-64-12	TB0044K	C001	1		S00854	BLU			ALL
A-R					0-0	32-64-12	TB0044K	A001	1		S00854	RED			ALL
A-Y					0-0	32-64-12	TB0044K	E001	1		S00854	YEL			ALL
W8036	286A8036				#2 NOSE GEAR DOWN SENSOR										
A-B					0-0	32-64-12	TB0046K	C001	1		S00853	BLU			ALL
A-R					0-0	32-64-12	TB0046K	A001	1		S00853	RED			ALL
A-Y					0-0	32-64-12	TB0046K	E001	1		S00853	YEL			ALL
W8038	286A8038				R ELEV DISC TO R ELEV POS XMTR AND R LOGO LIGHT										
0501	20	HL			18-11	33-49-11	D11108		2		D40190J	10			ALL
0502	20	HL			18-11	33-49-11	D11108		4		D40190J	7			ALL
0503	20	HL			18-11	33-49-11	D11108		5		D40190J	4			ALL
2201B	20	HM	KA		3-6	27-38-11	D03580		1		D40190J	1			YC051-YC060
2201B	20	HM	KA		2-7	27-38-11	D03580		1		D40190J	1			YC061-YR328
2201R	20	HM	KA		0-0	27-38-11	D03580		2		D40190J	2			ALL
3201B	20	HN	YA		3-6	27-38-11	D03580		5		D40190J	5			YC051-YC060
3201B	20	HN	YA		2-7	27-38-11	D03580		5		D40190J	5			YC061-YR328
3201R	20	HN	YA		0-0	27-38-11	D03580		4		D40190J	6			ALL
3201Y	20	HN	YA		0-0	27-38-11	D03580		3		D40190J	3			ALL

WIRE LIST

D280A108

91-21-11

Section W8030

Page 3 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To				Effectivity	
Wire No.	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
W8122	286A8122				FWD RIGHT SIDE WHEEL WELL AREA											
0501	20		HA		4-0	27-23-14	D46038P	10			D00816	3			YC051-YD152	
0501	20		HA		3-11	27-23-14	D46038P	10			D00816	3			YD153-YD158, YL951-YR323, YR325-YR328	
0502	20		HA		2-10	27-23-14	GD00324	DC..	E		D00816	2			YC051-YD152	
0502	20		HA		1-6	27-23-14	GD00324	DC..	E		D00816	2			YD153-YD158, YL951-YR323, YR325-YR328	
0503	20		HA		5-1	29-25-11	D46038P	9			D03242	3			YC051-YD152	
0503	20		HA		5-2	29-25-11	D46038P	9			D03242	3			YD153-YD158, YL951-YR323, YR325-YR328	
0504	20		HA		2-0	29-25-11	GD00314	DC..	E		D03242	2			YC051-YD152	
0504	20		HA		1-11	29-25-11	GD00314	DC..	E		D03242	2			YD153-YD158, YL951-YR323, YR325-YR328	
0505	20		HA		9-6	29-23-11	D46038P	11			D02860	11			YC051-YD152	
0505	20		HA		10-0	29-23-11	D46038P	11			D02860	11			YD153-YD158, YL951-YL963, YN231-YN235	
0505	20		HA		10-1	29-23-11	D46038P	11			D02860	11			YL964-YL999, YN236-YR323, YR325-YR328	
0506	20		CQ		9-8	29-23-11	D46038P	8			D02860	3			YC051-YD152	
0506	20		CQ		9-10	29-23-11	D46038P	8			D02860	3			YD153-YD158, YL951-YR323, YR325-YR328	
0507	20		HA		3-11	29-23-11	GD00318	DC..	E		D02860	9			YC051-YD152	
0507	20		HA		3-3	29-23-11	GD00318	DC..	E		D02860	9			YD153-YD158, YL951-YR323, YR325-YR328	
0508	20		CQ		4-1	29-23-11	GD00322	DC..	E		D02860	4			YC051-YD152	
0508	20		CQ		3-2	29-23-11	GD00322	DC..	E		D02860	4			YD153-YD158, YL951-YR323, YR325-YR328	
0509	20		HA		3-7	29-23-11	GD00318	DC..	E		D02860	2			YC051-YD152	
0509	20		HA		3-1	29-23-11	GD00318	DC..	E		D02860	2			YD153-YD158, YL951-YR323, YR325-YR328	

WIRE LIST

D280A108

91-21-11

Section W8120

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To					
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W8122	286A8122				FWD RIGHT SIDE WHEEL WELL AREA (continued)											
0510	20		HA		4-2	29-23-11	SP00112			9		D02860	1			YC051-YD152
0510	20		HA		4-5	29-23-11	SP00112			9		D02860	1			YD153-YD158, YL951-YR323, YR325-YR328
0511	20		HA		4-6	27-23-11	D46038P			14		D00820	3			YC051-YD152
0511	20		HA		4-4	27-23-11	D46038P			14		D00820	3			YD153-YD158, YL951-YR323, YR325-YR328
0512	20		HA		4-6	27-23-11	D46038P			13		D00820	2			YC051-YD152
0512	20		HA		4-4	27-23-11	D46038P			13		D00820	2			YD153-YD158, YL951-YR323, YR325-YR328
0513	20		HA		2-2	27-23-11	GD00324		DC..	E		D00820	1			YC051-YD152
0513	20		HA		2-0	27-23-11	GD00324		DC..	E		D00820	1			YD153-YD158, YL951-YR323, YR325-YR328
0515	18		HA		18-7	27-81-51	D10533			1		D46038P	19			YC051-YD152
0515	18		HA		16-5	27-81-51	D10533			1		D46038P	19			YD153-YD158, YL951-YR323, YR325-YR328
0516	18		HA		18-7	27-81-51	D10533			2		D46038P	23			YC051-YD152
0516	18		HA		16-5	27-81-51	D10533			2		D46038P	23			YD153-YD158, YL951-YR323, YR325-YR328
0530	20		HA		4-0	31-31-15	D00816			1		D46038P	3			YC065-YD152
0530	20		HA		3-11	31-31-15	D00816			1		D46038P	3			YD153-YD158, YL951-YR323, YR325-YR328
0542	18		HA		3-6	27-61-11	D46038P			15		D00758	2			YC051-YD152
0542	18		HA		3-4	27-61-11	D46038P			15		D00758	2			YD153-YD158, YL951-YR323, YR325-YR328
0543	18		HA		3-6	27-61-11	D46038P			27		D00758	3			YC051-YD152
0543	18		HA		3-4	27-61-11	D46038P			27		D00758	3			YD153-YD158, YL951-YR323, YR325-YR328
0544	18		HA		2-4	27-61-11	GD00324		DC..	E		D00758	1			YC051-YD152

WIRE LIST

D280A108

91-21-11
Section W8120
Page 2
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W8122	286A8122	FWD RIGHT SIDE WHEEL WELL AREA (continued)			
0544	18 HA	2-2 27-61-11	GD00324 DC.. E	D00758 1	YD153-YD158, YL951-YR323, YR325-YR328
3201B	20 HC YA	4-0 31-53-11	D46038P 5	D11728 2	YC051-YD152
3201B	20 HC YA	4-3 31-53-11	D46038P 5	D11728 2	YD153-YD158, YL951-YL963, YN231-YN235
3201B	20 HC YA	4-4 31-53-11	D46038P 5	D11728 2	YL964-YL999, YN236-YR323, YR325-YR328
3201R	20 HC YA	0-0 31-53-11	D46038P 6	D11728 1	YC051-YD158, YL951-YR323, YR325-YR328
3201Y	20 HC YA	0-0 31-53-11	D46038P 4	D11728 4	YC051-YD158, YL951-YR323, YR325-YR328
YAAF		0-0 27-81-51	D10533 S/R	GD02336 ST.. E	YC051-YD158, YL951-YR323, YR325-YR328
W8124	286A8124	AFT RIGHT SIDE WHEEL WELL AREA			
0501	20 HA	2-0 27-53-11	D46040P 17	D01014 1	YC051-YD158, YL951-YR328
0502	20 HA	2-0 27-53-11	D46040P 7	D01014 2	YC051-YD158, YL951-YR328
0503	20 HA	2-0 27-53-11	D46040P 16	D01014 3	YC051-YD158, YL951-YR328
0504	18 HA	1-10 27-53-11	GD00332 DC.. E	D01014 5	YC051-YD158, YL951-YR328
0505	20 HL	7-1 32-64-21	D14730 A	GD00332 DC.. E *2	YL955-YL999, YN236-YR328
0506	20 HL	7-2 32-64-21	D14730 C	D46040P 8	YL955-YL999, YN236-YR328
0507	20 HL	7-2 29-25-11	D14730 G	D46040P 19	YN236-YN501
0508	20 HL	7-2 29-25-11	D14730 H	D46040P 9	YN236-YN501
0509	20 HL	7-2 29-25-11	D14730 J	D46040P 6	YN236-YN501
0510	20 HL	7-1 32-64-21	D14730 S	GD00332 DC.. E *2	YL955-YL999, YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W8120

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W8124	286A8124				AFT RIGHT SIDE WHEEL WELL AREA (continued)										
0511	20		HL		7-2	32-64-21	D14730		U		D46040P	10			YL955-YL999, YN236-YR328
0512	20		HL		8-2	27-23-11	D46040P		15		D14360	A			YL955-YL963
0512	20		HL		8-1	27-23-11	D46040P		15		D14360	A			YL964-YL999, YN236-YR328
0513	20		HL		8-2	27-23-11	D46040P		5		D14360	C			YL955-YL963
0513	20		HL		8-1	27-23-11	D46040P		5		D14360	C			YL964-YL999, YN236-YR328
0514	20		HL		8-1	21-51-14	GD00332	DC..	E		D14360	D			YL955-YL999, YN236-YR328
0515	20		HL		8-2	21-51-14	D46040P		14		D14360	F			YL955-YL963
0515	20		HL		8-1	21-51-14	D46040P		14		D14360	F			YL964-YL999, YN236-YR328
0516	20		HL		8-2	27-31-11	D46040P		13		D14360	N			YL955-YL963
0516	20		HL		8-1	27-31-11	D46040P		13		D14360	N			YL964-YL999, YN236-YR328
0517	20		HL		8-2	27-31-11	D46040P		12		D14360	R			YL955-YL963
0517	20		HL		8-1	27-31-11	D46040P		12		D14360	R			YL964-YL999, YN236-YR328
0518	20		HL		8-2	29-25-11	D46040P		2		D14360	S			YL955-YL963
0518	20		HL		8-1	29-25-11	D46040P		2		D14360	S			YL964-YL999, YN236-YR328
0519	20		HL		8-2	29-25-11	D46040P		1		D14360	T			YL955-YL963
0519	20		HL		8-1	29-25-11	D46040P		1		D14360	T			YL964-YL999, YN236-YR328
0520	20		HL		8-2	29-25-11	D46040P		18		D14360	U			YL955-YL963
0520	20		HL		8-1	29-25-11	D46040P		18		D14360	U			YL964-YL999, YN236-YR328
A-AA					0-0	32-64-21	GD00332	DC..	E	*2	S00138	1			YC051-YD158, YL951-YL954, YN231-YN235
A-BB					0-0	32-64-21	S00138	CAP	Y		S00138	2			YC051-YD158, YL951-YL954, YN231-YN235
A-CC					0-0	32-64-21	D46040P		8		S00138	3			YC051-YD158, YL951-YL954, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W8120

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To													
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity				
W8124	286A8124	AFT RIGHT SIDE WHEEL WELL AREA (continued)															
A-DD			0-0	32-64-21	S00138	CAP	Y		S00138	4			YC051-YD158, YL951-YL954, YN231-YN235				
A-EE			0-0	32-64-21	S00138	CAP	Y		S00138	5			YC051-YD158, YL951-YL954, YN231-YN235				
A-FF			0-0	32-64-21	S00138	CAP	Y		S00138	6			YC051-YD158, YL951-YL954, YN231-YN235				
A-GG			0-0	29-25-11	D46040P		19		S00138	7			YC051-YD158, YL951-YL952, YN231-YN235				
A-GG			0-0	32-64-21	D46040P		19		S00138	7			YL953-YL954				
A-HH			0-0	29-25-11	D46040P		9		S00138	8			YC051-YD158, YL951-YL952, YN231-YN235				
A-HH			0-0	32-64-21	D46040P		9		S00138	8			YL953-YL954				
A-JJ			0-0	29-25-11	D46040P		6		S00138	9			YC051-YD158, YL951-YL952, YN231-YN235				
A-JJ			0-0	32-64-21	D46040P		6		S00138	9			YL953-YL954				
A-KK			0-0	32-64-21	S00138	CAP	Y		S00138	10			YC051-YD158, YL951-YL954, YN231-YN235				
A-LL			0-0	32-64-21	S00138	CAP	Y		S00138	11			YC051-YD158, YL951-YL954, YN231-YN235				
A-MM			0-0	32-64-21	S00138	CAP	Y		S00138	12			YC051-YD158, YL951-YL954, YN231-YN235				
A-NN			0-0	32-64-21	S00138	CAP	Y		S00138	13			YC051-YD158, YL951-YL954, YN231-YN235				
A-PP			0-0	32-64-21	S00138	CAP	Y		S00138	14			YC051-YD158, YL951-YL954, YN231-YN235				
A-RR			0-0	32-64-21	S00138	CAP	Y		S00138	15			YC051-YD158, YL951-YL954, YN231-YN235				

WIRE LIST

D280A108

91-21-11

Section W8120

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		Diagram	From			To			Effectivity		
	GA	CO	TY		FT-IN			Equip	Term	Type	Splice	Equip	Term		Type	Splice
W8124	286A8124				AFT RIGHT SIDE WHEEL WELL AREA (continued)											
A-SS					0-0	32-64-21	GD00332		DC..	E	*2	S00138	16			YC051-YD158, YL951-YL954, YN231-YN235
A-TT					0-0	32-64-21	S00138		CAP	Y		S00138	17			YC051-YD158, YL951-YL954, YN231-YN235
A-UU					0-0	32-64-21	D46040P		10			S00138	18			YC051-YD158, YL951-YL954, YN231-YN235
B-AA					0-0	27-23-11	D46040P		15			S01051	1			YC051-YD158, YL951-YL954, YN231-YN235
B-BB					0-0	27-23-11	S01051		CAP	Y		S01051	2			YC051-YD158, YL951-YL954, YN231-YN235
B-CC					0-0	27-23-11	D46040P		5			S01051	3			YC051-YD158, YL951-YL954, YN231-YN235
B-DD					0-0	21-51-14	GD00332		DC..	E		S01051	4			YC051-YD158, YL951-YL954, YN231-YN235
B-EE					0-0	21-51-14	S01051		CAP	Y		S01051	5			YC051-YD158, YL951-YL954, YN231-YN235
B-FF					0-0	21-51-14	D46040P		14			S01051	6			YC051-YD158, YL951-YL954, YN231-YN235
B-GG					0-0	27-23-11	GD00332		DC..	E		S01051	7			YC051-YC057
B-GG					0-0	27-23-11	S01051		CAP	Y		S01051	7			YC058-YD158, YL951-YL954, YN231-YN235
B-HH					0-0	27-23-11	D46040P		3			S01051	8			YC051-YC057
B-HH					0-0	27-23-11	S01051		CAP	Y		S01051	8			YC058-YD158, YL951-YL954, YN231-YN235
B-JJ					0-0	27-23-11	S01051		CAP	Y		S01051	9			YC051-YD158, YL951-YL954, YN231-YN235

WIRE LIST
D280A108

91-21-11
Section W8120
Page 6
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To					
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W8124	286A8124				AFT RIGHT SIDE WHEEL WELL AREA (continued)											
B-KK					0-0	27-23-11	S01051		CAP	Y		S01051		10		YC051-YD158, YL951-YL954, YN231-YN235
B-LL					0-0	27-23-11	S01051		CAP	Y		S01051		11		YC051-YD158, YL951-YL954, YN231-YN235
B-MM					0-0	27-23-11	S01051		CAP	Y		S01051		12		YC051-YD158, YL951-YL954, YN231-YN235
B-NN					0-0	27-31-11	D46040P				13	S01051		13		YC051-YD158, YL951-YL954, YN231-YN235
B-PP					0-0	27-31-11	S01051		CAP	Y		S01051		14		YC051-YD158, YL951-YL954, YN231-YN235
B-RR					0-0	27-31-11	D46040P				12	S01051		15		YC051-YD158, YL951-YL954, YN231-YN235
B-SS					0-0	29-25-11	D46040P				2	S01051		16		YC051-YD158, YL951-YL954, YN231-YN235
B-TT					0-0	29-25-11	D46040P				1	S01051		17		YC051-YD158, YL951-YL954, YN231-YN235
B-UU					0-0	29-25-11	D46040P				18	S01051		18		YC051-YD158, YL951-YL954, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W8120

Page 7 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I W8137	286A8137			VOR ANTENNA RIGHT - STA 1035 TO RF PWR DIV-2											
I 001CO				AA	0-0	34-51-21	D03783	=	C1		D04437J	=	C1		ALL
I 001CX			0H	AA	115-7	34-51-21	D03783	=	A1		D04437J	=	A1		YC051-YL999, YR301-YR328 YN231-YN501
001CX			0H	AA	96-2	34-51-21	D03783	=	A1		D04437J	=	A1		

WIRE LIST
D280A108

91-21-11
Section W8130
Page 1 End
Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description	From			To				Effectivity				
	GA	CO	TY		Fam	FT-IN	Diagram	Equip	Term	Type	Splice		Equip	Term	Type	Splice
Wire No.																
I	W8144	286A8144			NOSE GEAR TAXI LIGHT											
I	0001	16		HA		0-1	33-45-11	TB0040K	G001	1		L00170	=P	GW		ALL
I	0002	16		HA		0-1	33-45-11	TB0040K	G002	1		L00170	=G	GW		ALL

For training purposes only!

WIRE LIST

D280A108

91-21-11

Section W8140

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
							Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
I	W8153	286A8153				VOR ANT RIGHT-XMSN CABLE									
I	001CO			AA	0-0	34-51-21	D00091		= C1		D04437P		= C1		ALL
I	001CX		0H	AA	30-7	34-51-21	D00091		= A1		D04437P		= A1		ALL
I	W8157	286A8157				GLIDE SLOPE ANT RIGHT - STA 178 TO ANT									
I	001CO			AA	0-0	34-31-21	D02131		= C1		D03315		= C1		ALL
I	001CX		0F	AA	1-10	34-31-21	D02131		= A1		D03315		= A1		ALL
I	W8159	286A8159				G/S ANT RIGHT-STA 178 TO ANT									
I	001CO			AA	0-0	34-31-21	D00087		= C1		D03311		= C1		ALL
I	001CX		0F	AA	3-1	34-31-21	D00087		= A1		D03311		= A1		YC051-YC063
I	001CX		0F	AA	6-9	34-31-21	D00087		= A1		D03311		= A1		YC064-YR328

WIRE LIST

D280A108

91-21-11

Section W8150

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice	
W8222	286A8222	FWD RIGHT SIDE WHEEL WELL AREA			
0501	20 HA	4-8 29-33-11	D46042P 1	D02682 2	YC051-YD158, YL951-YL968, YN231-YR328
0502	18 HA	7-4 29-11-11	D46042P 6	D00764 A	YC051-YD158, YL951-YL968, YN231-YR328
0503	18 HA	7-4 29-11-11	D46042P 7	D00764 B	YC051-YD158, YL951-YL968, YN231-YR328
0504	18 HA	4-10 29-32-11	D46042P 4	D00660 3	YC051-YD152
0504	18 HA	5-3 29-32-11	D46042P 4	D00660 3	YD153-YD158, YL951-YL963, YN231-YN235
0504	18 HA	5-2 29-32-11	D46042P 4	D00660 3	YL964-YL968, YN236-YR328
0505	18 HA	4-10 29-32-11	D46042P 3	D00660 2	YC051-YD152
0505	18 HA	5-3 29-32-11	D46042P 3	D00660 2	YD153-YD158, YL951-YL963, YN231-YN235
0505	18 HA	5-2 29-32-11	D46042P 3	D00660 2	YL964-YL968, YN236-YR328
0506	20 HA	5-2 29-33-11	D46042P 2	D02686 3	YC051-YD158, YL951-YL968, YN231-YR328
0507	20 HA	3-3 29-33-11	GD00312 DC.. E	D02686 2	YC051-YD158, YL951-YL968, YN231-YR328
0508	18 HA	10-7 29-11-11	GD00312 DC.. E	D00764 E	YC051-YD158, YL951-YL968, YN231-YR328
0509	18 HA	2-9 29-32-11	GD00336 ST.. E	D00660 1	YC051-YD152
0509	18 HA	2-8 29-32-11	GD00336 ST.. E	D00660 1	YD153-YD158, YL951-YL968, YN231-YR328
0511	20 HA	2-11 29-33-11	GD00312 DC.. E	D02682 3	YC051-YD158, YL951-YL968, YN231-YR328

WIRE LIST

D280A108

91-21-11

Section W8220

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W8222	286A8222				FWD RIGHT SIDE WHEEL WELL AREA (continued)										
0513	18		HA		7-4	31-62-24	D00764		D		D46042P	8			YC051-YD158, YL951-YL968, YN231-YR328
6001R	18		9P		3-5	26-12-11	D46042P		9		D00842	= 1			YC051-YD152
6001R	18		9P		3-0	26-12-11	D46042P		9		D00842	= 1			YD153-YD158
6001R	18		9P		2-11	26-12-11	D46042P		9		M00270	= A	N		YL951-YL968, YN231-YR328
6011	18		PA		9-3	28-21-11	D46042P		5		SP00426		9		YC051-YD152
6011	18		PA		10-4	28-21-11	D46042P		5		SP00426		9		YD153-YD158, YL951-YL963, YN231-YN235
6011	18		PA		10-6	28-21-11	D46042P		5		SP00426		9		YL964-YL968, YN236-YR328
W8224	286A8224				AFT RIGHT SIDE WHEEL WELL AREA										
0501	20		HA		8-1	29-23-11	D40004P		15		D02674	5			YC051-YD152
0501	20		HA		6-6	29-23-11	D40004P		15		D02674	5			YD153-YL963, YN231-YN235
0501	20		HA		10-8	29-23-11	D40004P		15		D02674	5			YL964-YL999, YN236-YR328
0502	20		HA		8-1	29-31-11	D40004P		12		D02674	1			YC051-YD152
0502	20		HA		6-6	29-31-11	D40004P		12		D02674	1			YD153-YL963, YN231-YN235
0502	20		HA		10-8	29-31-11	D40004P		12		D02674	1			YL964-YL999, YN236-YR328
0503	20		HA		8-1	29-31-11	D40004P		13		D02674	2			YC051-YD152
0503	20		HA		6-6	29-31-11	D40004P		13		D02674	2			YD153-YL963, YN231-YN235
0503	20		HA		10-8	29-31-11	D40004P		13		D02674	2			YL964-YL999, YN236-YR328
0504	20		HA		8-1	29-31-11	D40004P		14		D02674	3			YC051-YD152
0504	20		HA		6-6	29-31-11	D40004P		14		D02674	3			YD153-YL963, YN231-YN235
0504	20		HA		10-8	29-31-11	D40004P		14		D02674	3			YL964-YL999, YN236-YR328
0505	20		HA		1-10	29-23-11	GD00328	DC..	E		D02674	4			YC051-YC058
0505	20		HA		2-0	29-23-11	GD00328	DC..	E		D02674	4			YC059-YD152
0505	20		HA		1-7	29-23-11	GD00328	DC..	E		D02674	4			YD153-YR328
0510	20		HA		4-0	29-31-11	GD00190	ST..	E		D02674	6			YC051-YC058

WIRE LIST

D280A108

91-21-11

Section W8220

Page 2

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W8224		286A8224			AFT RIGHT SIDE WHEEL WELL AREA (continued)											
0510		20		HA		3-10	29-31-11	GD00190	ST..	E		D02674	6			YC059-YD152
0510		20		HA		2-4	29-31-11	GD01966	ST..	E		D02674	6			YD153-YR328
0523		18		PA		2-0	32-64-12	GD02064	AC..	E		D46018J	3			YC051-YC058
0523		18		PA		2-6	32-64-12	GD02064	AC..	E		D46018J	3			YC059-YD152
0523		18		PA		8-11	32-64-12	GD02076	AC..	E	*	D46018J	3			YD153-YL963, YL969-YN235, YN237-YN260, YR307-YR328
0523		18		PA		8-7	32-64-12	GD02076	AC..	E	*	D46018J	3			YL964-YL968, YN236, YN501-YR306
0541		18		PA		2-6	32-31-12	GD02062	AC..	E		D46016J	7			YC051-YC058
0541		18		PA		2-7	32-31-12	GD02062	AC..	E		D46016J	7			YC059-YD152
0541		18		PA		14-0	32-31-12	GD02076	AC..	E	*	D46016J	7			YD153-YD158, YN231
0541		18		PA		14-1	32-31-12	GD02076	AC..	E	*	D46016J	7			YD160-YL963, YN232-YN235
0541		18		PA		13-10	32-31-12	GD02076	AC..	E	*	D46016J	7			YL964-YL968, YN236, YN501-YR306
0541		18		PA		14-2	32-31-12	GD02076	AC..	E	*	D46016J	7			YL969-YL999, YR307-YR317
0541		18		PA		14-4	32-31-12	GD02076	AC..	E	*	D46016J	7			YN237-YN260, YR318-YR328
2211B		20		M2	KK	14-1	32-41-11	D40004P		4		D46016J	3			YC051-YC058
2211B		20		M2	KK	14-4	32-41-11	D40004P		4		D46016J	3			YC059-YD152
2211B		20		M2	KK	15-3	32-41-11	D40004P		4		D46016J	3			YD153-YD158, YN231
2211B		20		M2	KK	15-5	32-41-11	D40004P		4		D46016J	3			YD160-YL963, YL969-YL999, YN232-YN235, YR307-YR317
2211B		20		M2	KK	15-1	32-41-11	D40004P		4		D46016J	3			YL964-YL968, YN236, YN501-YR306
2211B		20		M2	KK	15-7	32-41-11	D40004P		4		D46016J	3			YN237-YN260, YR318-YR328
2211R		20		M2	KK	0-0	32-41-11	D40004P		3		D46016J	1			ALL
2211ZI					KK	0-0	32-41-11	D40004P		5		D46016J	2			ALL
2211ZO					KK	0-0	32-41-11	D40004P		S/R		D46016J	S/R			ALL
2223B		20		HQ	KX	8-8	32-64-12	D40004P		7		D46018J	2			YC051-YC058
2223B		20		HQ	KX	9-3	32-64-12	D40004P		7		D46018J	2			YC059-YD152
2223B		20		HQ	KX	10-2	32-64-12	D40004P		7		D46018J	2			YD153-YL963, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W8220

Page 3

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To											
Wire No.	GA CO TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity		
W8224	286A8224	AFT RIGHT SIDE WHEEL WELL AREA (continued)													
2223B	20	HQ	KX	9-11	32-64-12	D40004P	7		D46018J	2			YL964-YL968, YN236, YN501-YR306		
2223B	20	HQ	KX	10-3	32-64-12	D40004P	7		D46018J	2			YL969-YL999, YN237-YN260, YR307-YR328		
2223R	20	HQ	KX	0-0	32-64-12	D40004P	6		D46018J	1			ALL		
2223Z			KX	0-0	32-64-12	D40004P	S/R		D46018J	S/R			ALL		
2224B	20	HB	KY	6-7	32-64-12	D40004P	2		SP00354		9		YC051-YD152		
2224B	20	HB	KY	6-11	32-64-12	D40004P	2		SP00354		9		YD153-YL963, YN231-YN235		
2224B	20	HB	KY	10-0	32-64-12	D40004P	2		SP00354		9		YL964-YL999, YN236-YR328		
2224R	20	HB	KY	0-0	32-64-12	D40004P	1		SP00352		9		ALL		
2241B	20	HQ	LQ	14-1	32-31-12	D40004P	10		D46016J	6			YC051-YC058		
2241B	20	HQ	LQ	14-4	32-31-12	D40004P	10		D46016J	6			YC059-YD152		
2241B	20	HQ	LQ	15-3	32-31-12	D40004P	10		D46016J	6			YD153-YD158, YN231		
2241B	20	HQ	LQ	15-5	32-31-12	D40004P	10		D46016J	6			YD160-YL963, YL969-YL999, YN232-YN235, YR307-YR317		
2241B	20	HQ	LQ	15-1	32-31-12	D40004P	10		D46016J	6			YL964-YL968, YN236, YN501-YR306		
2241B	20	HQ	LQ	15-7	32-31-12	D40004P	10		D46016J	6			YN237-YN260, YR318-YR328		
2241R	20	HQ	LQ	0-0	32-31-12	D40004P	9		D46016J	5			ALL		
2241Z			LQ	0-0	32-31-12	D40004P	S/R		D46016J	S/R			ALL		
A-B				0-0	32-64-12	S01017	BLU		SP00354		9		ALL		
A-R				0-0	32-64-12	S01017	RED		SP00352		9		ALL		
A-Y				0-0	32-64-12	S01017	YEL		GD01950	AC..	E		YC051-YD152		
A-Y				0-0	32-64-12	S01017	YEL		GD01960	AC..	E		YD153-YL963, YN231-YN235		
A-Y				0-0	32-64-12	S01017	YEL		GD00092	AC..	E		YL964-YL999, YN236-YR328		
W8226	286A8226	AFT RIGHT SIDE, WHEEL WELL													
0501	18	HA		3-6	27-54-11	D46044P	3		D01582	1			ALL		
0503	18	HA		3-6	27-54-11	D01582	2		D46044P	14			ALL		
0504	20	HL		5-3	27-53-12	GD00310	DC.. E	*	D14362	A			YL955-YL999, YN236-YR328		

WIRE LIST

D280A108

91-21-11

Section W8220

Page 4

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W8226	286A8226			AFT RIGHT SIDE, WHEEL WELL (continued)											
0505	20		HL		4-10	27-53-12	D46044P	12			D14362	C			YL955-YL999, YN236-YR328
0506	20		HL		5-3	22-23-12	GD00310	DC..	E		D14362	D			YL955-YL999, YN236-YR328
0507	20		HL		4-10	22-23-12	D40006P	1			D14362	E			YL955-YL999, YN236-YR328
0508	20		HL		5-3	33-25-11	GD00310	DC..	E	*	D14362	G			YL955-YL999, YN236-YR328
0509	20		HL		4-10	33-25-11	D40006P	2			D14362	H			YL955-YL999, YN236-YR328
0510	20		HL		4-10	27-41-12	D46044P	6			D14362	N			YL955-YL999, YN236-YR328
0511	20		HL		4-10	27-41-12	D46044P	7			D14362	P			YL955-YL999, YN236-YR328
0512	20		HL		4-10	27-41-12	D46044P	8			D14362	R			YL955-YL999, YN236-YR328
0513	20		HL		4-10	27-41-12	D46044P	10			D14362	S			YL955-YL999, YN236-YR328
0514	20		HL		4-10	27-41-12	D46044P	9			D14362	U			YL955-YL999, YN236-YR328
A-AA					0-0	27-53-12	GD00310	DC..	E	*	S00245	1			YC051-YL954, YN231-YN235
A-BB					0-0	27-53-12	S00245	CAP	Y		S00245	2			YC051-YL954, YN231-YN235
A-CC					0-0	27-53-12	D46044P	12			S00245	3			YC051-YL954, YN231-YN235
A-DD					0-0	22-23-12	GD00310	DC..	E		S00245	4			YC051-YL954, YN231-YN235
A-EE					0-0	22-23-12	D40006P	1			S00245	5			YC051-YL954, YN231-YN235
A-FF					0-0	22-23-12	S00245	CAP	Y		S00245	6			YC051-YL954, YN231-YN235
A-GG					0-0	33-25-11	GD00310	DC..	E	*	S00245	7			YC051-YL954, YN231-YN235
A-HH					0-0	33-25-11	D40006P	2			S00245	8			YC051-YL954, YN231-YN235
A-JJ					0-0	33-25-11	S00245	CAP	Y		S00245	9			YC051-YL954, YN231-YN235

WIRE LIST

D280A108

91-21-11

Section W8220

Page 5

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description		From				To					
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W8226	286A8226			AFT RIGHT SIDE, WHEEL WELL (continued)											
A-KK					0-0	27-53-12	S00245		CAP	Y	S00245	10			YC051-YL954, YN231-YN235
A-LL					0-0	27-53-12	S00245		CAP	Y	S00245	11			YC051-YL954, YN231-YN235
A-MM					0-0	27-53-12	S00245		CAP	Y	S00245	12			YC051-YL954, YN231-YN235
A-NN					0-0	27-41-12	D46044P		6		S00245	13			YC051-YL954, YN231-YN235
A-PP					0-0	27-41-12	D46044P		7		S00245	14			YC051-YL954, YN231-YN235
A-RR					0-0	27-41-12	D46044P		8		S00245	15			YC051-YL954, YN231-YN235
A-SS					0-0	27-41-12	D46044P		10		S00245	16			YC051-YL954, YN231-YN235
A-TT					0-0	27-41-12	S00245		CAP	Y	S00245	17			YC051-YL954, YN231-YN235
A-UU					0-0	27-41-12	D46044P		9		S00245	18			YC051-YL954, YN231-YN235
B-AA					0-0	27-53-12	GD00310		DC..	E	S00246	1			ALL
B-BB					0-0	27-53-12	S00246		CAP	Y	S00246	2			ALL
B-CC					0-0	27-53-12	D46044P		13		S00246	3			ALL
B-DD					0-0	27-53-12	S00246		CAP	Y	S00246	4			ALL
B-EE					0-0	27-53-12	S00246		CAP	Y	S00246	5			ALL
B-FF					0-0	27-53-12	S00246		CAP	Y	S00246	6			ALL
W8228	286A8228			FWD LEFT SIDE WHEEL WELL AREA											
0501	18		HA		3-6	27-62-21	D46046P		6	18	D11730	1			YC051-YD152, YL964-YL999, YN236-YR328
0501	18		HA		3-4	27-62-21	D46046P		6	18	D11730	1			YD153-YD158, YN231-YN235
0501	18		HA		3-7	27-62-21	D46046P		6	18	D11730	1			YD160-YL963
0502	18		HA		7-1	31-53-11	GD00312		DC..	E	D11730	2			YC051-YD152
0502	18		HA		6-8	31-53-11	GD00312		DC..	E	D11730	2			YD153-YD158, YN231-YN235
0502	18		HA		6-11	31-53-11	GD00312		DC..	E	D11730	2			YD160-YL999, YN236-YR328

WIRE LIST

D280A108

91-21-11

Section W8220

Page 6

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number	Description	From	To	Effectivity
Wire No.	GA CO TY	Fam	FT-IN Diagram	Equip Term Type Splice	Equip Term Type Splice
W8228	286A8228	FWD LEFT SIDE WHEEL WELL AREA (continued)			
0503	18	HA	3-6 31-53-11	D11730 3	D46046P 5 18 YC051-YD152, YL964-YL999, YN236-YR328
0503	18	HA	3-4 31-53-11	D11730 3	D46046P 5 18 YD153-YD158, YN231-YN235
0503	18	HA	3-7 31-53-11	D11730 3	D46046P 5 18 YD160-YL963
0504	20	PA	1-6 27-62-11	D13938 S/R	GD01038 ST.. E YL953-YL999, YR301-YR328
0506	20	PA	1-7 27-62-11	D13938 B	GD01036 DC.. E YL953-YL963
0506	20	PA	1-10 27-62-11	D13938 B	GD01036 DC.. E YL964-YL999, YR301-YR328
0513	18	PA	2-11 32-64-11	GD02066 AC.. E	D46012J 3 YC051-YD152
0513	18	PA	14-2 32-64-11	GD02080 AC.. E	D46012J 3 YD153-YL963, YN231-YN235
0513	18	PA	16-6 32-64-11	GD02080 AC.. E	D46012J 3 YL964-YL999, YN236-YR328
0540	18	PA	2-8 32-31-11	GD02066 AC.. E	D46014J 7 YC051-YD152
0540	18	PA	14-0 32-31-11	GD02080 AC.. E	D46014J 7 YD153-YL963, YN231-YN235
0540	18	PA	16-4 32-31-11	GD02080 AC.. E	D46014J 7 YL964-YL999, YN236-YR328
1006	20	X1 AB	4-9 27-62-11	D13938 A	D46046P 32 YL953-YL999, YR301-YR328
1006Z		AB	0-0 27-62-11	D13938 S/R	D46046P S/R YL953-YL999, YR301-YR328
1007	20	X1 AG	4-9 27-62-11	D13938 C	D46046P 33 YL953-YL999, YR301-YR328
1007Z		AG	0-0 27-62-11	D13938 S/R	D46046P S/R YL953-YL999, YR301-YR328
2201B	20	HF KA	6-8 32-41-11	D46046P 8	D02872 2 YC051-YD152
2201B	20	HF KA	6-1 32-41-11	D46046P 8	D02872 2 YD153-YL963, YN231-YN235
2201B	20	HF KA	6-2 32-41-11	D46046P 8	D02872 2 YL964-YL999, YN236-YR328
2201R	20	HF KA	0-0 32-41-11	D46046P 7	D02872 1 ALL
2201Z		KA	0-0 32-41-11	D46046P S/R	D02872 S/R ALL
2211B	20	M2 KK	8-6 32-41-11	D46046P 29	D46014J 3 YC051-YD152
2211B	20	M2 KK	8-7 32-41-11	D46046P 29	D46014J 3 YD153-YR328
2211R	20	M2 KK	0-0 32-41-11	D46046P 28	D46014J 1 ALL

WIRE LIST

D280A108

91-21-11

Section W8220

Page 7

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Fam	Description		From				To				
	GA	CO	TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W8228	286A8228			FWD LEFT SIDE WHEEL WELL AREA (continued)											
2211ZI				KK	0-0	32-41-11	D46046P	30	18		D46014J	2			ALL
2211ZO				KK	0-0	32-41-11	D46046P		S/R		D46014J		S/R		ALL
2213B	20	HQ		KM	8-8	32-64-11	D46046P	12			D46012J	2			YC051-YD152
2213B	20	HQ		KM	8-9	32-64-11	D46046P	12			D46012J	2			YD153-YL963, YN231-YN235
2213B	20	HQ		KM	8-10	32-64-11	D46046P	12			D46012J	2			YL964-YL999, YN236-YR328
2213R	20	HQ		KM	0-0	32-64-11	D46046P	11			D46012J	1			ALL
2213Z				KM	0-0	32-64-11	D46046P		S/R		D46012J		S/R		ALL
2214B	20	HB		KN	7-8	32-64-11	D46046P	2			SP00364		9		YC051-YD152
2214B	20	HB		KN	8-2	32-64-11	D46046P	2			SP00364		9		YD153-YL963, YN231-YN235
2214B	20	HB		KN	7-9	32-64-11	D46046P	2			SP00364		9		YL964-YL999, YN236-YR328
2214R	20	HB		KN	0-0	32-64-11	D46046P	1			SP00362		9		ALL
2240B	20	HQ		LP	8-6	32-31-11	D46046P	15			D46014J	6			YC051-YD152
2240B	20	HQ		LP	8-7	32-31-11	D46046P	15			D46014J	6			YD153-YR328
2240R	20	HQ		LP	0-0	32-31-11	D46046P	14			D46014J	5			ALL
2240Z				LP	0-0	32-31-11	D46046P		S/R		D46014J		S/R		ALL
2601B	20	HQ		SA	10-7	78-34-21	D46046P	19			D03056	7			YC051-YD152
2601B	20	HQ		SA	11-7	78-34-21	D46046P	19			D03056	7			YD153-YL963, YN231-YN235
2601B	20	HQ		SA	11-8	78-34-21	D46046P	19			D03056	7			YL964-YL999, YN236-YR328
2601R	20	HQ		SA	0-0	78-34-21	D46046P	18			D03056	2			ALL
2601Z				SA	0-0	78-34-21	D46046P		S/R		GD00756		ST..	E	ALL
2602B	20	HQ		SB	10-7	78-34-21	D46046P	17			D03056	5			YC051-YD152
2602B	20	HQ		SB	11-7	78-34-21	D46046P	17			D03056	5			YD153-YL963, YN231-YN235
2602B	20	HQ		SB	11-8	78-34-21	D46046P	17			D03056	5			YL964-YL999, YN236-YR328
2602R	20	HQ		SB	0-0	78-34-21	D46046P	16			D03056	4			ALL
2602Z				SB	0-0	78-34-21	D46046P		S/R		GD00756		ST..	E	ALL
2603B	20	HQ		SC	10-7	78-34-21	D46046P	20			D03056	6			YC051-YD152
2603B	20	HQ		SC	11-7	78-34-21	D46046P	20			D03056	6			YD153-YL963, YN231-YN235
2603B	20	HQ		SC	11-8	78-34-21	D46046P	20			D03056	6			YL964-YL999, YN236-YR328
2603R	20	HQ		SC	0-0	78-34-21	D46046P	21			D03056	3			ALL

WIRE LIST

D280A108

91-21-11

Section W8220

Page 8

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W8228		286A8228			FWD LEFT SIDE WHEEL WELL AREA (continued)											
2603Z					SC	0-0	78-34-21	D46046P	S/R			GD00756	ST..	E		ALL
3601B		20		HG	A4	10-9	78-36-21	D46046P	24			D03058	4			YC051-YD152
3601B		20		HG	A4	11-6	78-36-21	D46046P	24			D03058	4			YD153-YL963, YN231-YN235
3601B		20		HG	A4	11-8	78-36-21	D46046P	24			D03058	4			YL964-YL999, YN236-YR328
3601R		20		HG	A4	0-0	78-36-21	D46046P	22			D03058	2			ALL
3601Y		20		HG	A4	0-0	78-36-21	D46046P	23			D03058	3			ALL
3601Z					A4	0-0	78-36-21	D46046P	S/R			GD00756	ST..	E	*	ALL
3602B		20		HG	B4	10-9	78-36-21	D46046P	27			D03058	7			YC051-YD152
3602B		20		HG	B4	11-6	78-36-21	D46046P	27			D03058	7			YD153-YL963, YN231-YN235
3602B		20		HG	B4	11-8	78-36-21	D46046P	27			D03058	7			YL964-YL999, YN236-YR328
3602R		20		HG	B4	0-0	78-36-21	D46046P	25			D03058	5			ALL
3602Y		20		HG	B4	0-0	78-36-21	D46046P	26			D03058	6			ALL
3602Z					B4	0-0	78-36-21	D46046P	S/R			GD00756	ST..	E	*	ALL
A-B						0-0	32-64-11	SP00364		9		S00074	BLU			ALL
A-R						0-0	32-64-11	SP00362		9		S00074	RED			ALL
A-Y						0-0	32-64-11	GD01950	AC..	E		S00074	YEL			ALL

WIRE LIST

D280A108

91-21-11

Section W8220

Page 9 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W8230	286A8230			AFT LEFT SIDE WHEEL WELL AREA											
0501	18		HL		3-5	32-42-11	D02570		3		GD00304	ST..	E		YC051-YD152
0501	18		HL		2-5	32-42-11	D02570		3		GD01968	ST..	E		YD153-YR328
1001	20		HE	AA	3-9	31-31-15	D46048P		16		D02572		3		YC051-YD152
1001	20		HE	AA	3-11	31-31-15	D46048P		16		D02572		3		YD153-YR328
1001Z				AA	0-0	31-31-15	D46048P		S/R		D02572	DED			ALL
2201B	18		HF	KA	4-4	32-41-11	D46048P		5		D00930		2		ALL
2201R	18		HF	KA	0-0	32-41-11	D46048P		4		D00930		1		ALL
2201Z				KA	0-0	32-41-11	D46048P		S/R		D00930	S/R			ALL
2202B	20		HF	KB	3-9	32-42-11	D46048P		7		D02572		2		YC051-YD152
2202B	20		HF	KB	3-11	32-42-11	D46048P		7		D02572		2		YD153-YR328
2202R	20		HF	KB	0-0	32-42-11	D46048P		6		D02572		1		ALL
2202Z				KB	0-0	32-42-11	D46048P		S/R		D02572	DED			ALL
2203B	20		HF	KC	4-0	32-42-11	D46048P		14		D02574		2		YC051-YD152
2203B	20		HF	KC	4-1	32-42-11	D46048P		14		D02574		2		YD153-YR328
2203R	20		HF	KC	0-0	32-42-11	D46048P		13		D02574		1		ALL
2203Z				KC	0-0	32-42-11	D46048P		15		D02574	DED			ALL
2204B	20		HF	KD	5-0	32-42-11	D46048P		11		D02576		3		YC051-YD152
2204B	20		HF	KD	4-9	32-42-11	D46048P		11		D02576		3		YD153-YR328
2204R	20		HF	KD	0-0	32-42-11	D46048P		10		D02576		2		ALL
2204Z				KD	0-0	32-42-11	D46048P		S/R		D02576	DED			ALL
2205B	20		HF	KE	4-0	32-42-11	D46048P		2		D02570		2		YC051-YD152
2205B	20		HF	KE	3-8	32-42-11	D46048P		2		D02570		2		YD153-YR328
2205R	20		HF	KE	0-0	32-42-11	D46048P		1		D02570		1		ALL
2205Z				KE	0-0	32-42-11	D46048P		S/R		D02570	DED			ALL
W8234	286A8234			#1 RIGHT GEAR ON GROUND/OUTBD ANTISKID XDCR											
2201B	20		Y6	KA	0-0	32-41-11	D11126		3		TB0006K	G002	1		ALL
2201R	20		Y6	KA	0-0	32-41-11	D11126		1		TB0006K	E002	1		ALL
2201Z				KA	0-0	32-41-11	D11126		DED		TB0006L	A003	1		ALL
2211B	18		HQ	KK	0-0	32-41-11	D46014P		3		TB0006K	G002	1		ALL
2211R	18		HQ	KK	0-0	32-41-11	D46014P		1		TB0006K	E002	1		ALL
2211Z				KK	0-0	32-41-11	D46014P		2		TB0006L	A003	1		ALL
3201B	18		HN	YA	0-0	32-31-11	D46014P		6		TB0006K	C001	1		ALL
3201R	18		HN	YA	0-0	32-31-11	D46014P		5		TB0006K	A001	1		ALL
3201Y	18		HN	YA	0-0	32-31-11	D46014P		7		TB0006K	E001	1		ALL
A-B					0-0	32-31-11	TB0006K		C001	1	S01010	BLU			ALL
A-R					0-0	32-31-11	TB0006K		A001	1	S01010	RED			ALL
A-Y					0-0	32-31-11	TB0006K		E001	1	S01010	YEL			ALL

WIRE LIST

D280A108

91-21-11

Section W8230

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.		Part Number			Description			From				To				
Wire No.		GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W8236		286A8236					#2 RIGHT GEAR ON GROUND/INBD ANTISKID XDCR									
2201B		20	Y6	KA		0-0	32-41-11	D11124		3		TB0008K	G002	1		ALL
2201R		20	Y6	KA		0-0	32-41-11	D11124		1		TB0008K	E002	1		ALL
2201Z				KA		0-0	32-41-11	D11124		DED		TB0008L	A003	1		ALL
2211B		18	HQ	KK		0-0	32-41-11	D46016P		3		TB0008K	G002	1		ALL
2211R		18	HQ	KK		0-0	32-41-11	D46016P		1		TB0008K	E002	1		ALL
2211Z				KK		0-0	32-41-11	D46016P		2		TB0008L	A003	1		ALL
3201B		18	HN	YA		0-0	32-31-12	D46016P		6		TB0008K	C001	1		ALL
3201R		18	HN	YA		0-0	32-31-12	D46016P		5		TB0008K	A001	1		ALL
3201Y		18	HN	YA		0-0	32-31-12	D46016P		7		TB0008K	E001	1		ALL
A-B						0-0	32-31-12	TB0008K		C001	1	S01011	BLU			ALL
A-R						0-0	32-31-12	TB0008K		A001	1	S01011	RED			ALL
A-Y						0-0	32-31-12	TB0008K		E001	1	S01011	YEL			ALL

WIRE LIST

D280A108

91-21-11

Section W8230

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To				Effectivity	
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice		
I	W8489	286A8489	WEATHER RADAR ANTENNA HONEYWELL													
I	0001	20		GK		3-1	34-41-11	D01409		27			D00119	HH		YC051-YD170
I	0001	20		GK		3-2	34-41-11	D01409		27			D00119	HH		YL951-YR328
I	0002	20		GK		3-1	34-41-11	D01409		28			D00119	N-		YC051-YD170
I	0002	20		GK		3-2	34-41-11	D01409		28			D00119	N-		YL951-YR328
I	2001B	20		Y6	A	3-1	34-41-11	D01409		4			D00119	T-		YC051-YD170
I	2001B	20		Y6	A	3-2	34-41-11	D01409		4			D00119	T-		YL951-YR328
I	2001R	20		Y6	A	0-0	34-41-11	D01409		5			D00119	S-		ALL
I	2001Z				A	0-0	34-41-11	D01409		3			D00119	DED		ALL
I	2002B	20		Y6	B	3-1	34-41-11	D01409		16			D00119	Q-		YC051-YD170
I	2002B	20		Y6	B	3-2	34-41-11	D01409		16			D00119	Q-		YL951-YR328
I	2002R	20		Y6	B	0-0	34-41-11	D01409		17			D00119	P-		ALL
I	2002Z				B	0-0	34-41-11	D01409		15			D00119	DED		ALL
I	2003B	20		Y6	C	3-1	34-41-11	D01409		9			D00119	V-		YC051-YD170
I	2003B	20		Y6	C	3-2	34-41-11	D01409		9			D00119	V-		YL951-YR328
I	2003R	20		Y6	C	0-0	34-41-11	D01409		10			D00119	U-		ALL
I	2003Z				C	0-0	34-41-11	D01409		21			D00119	DED		ALL
I	2004B	20		Y6	D	3-1	34-41-11	D01409		33			D00119	Y		YC051-YD170
I	2004B	20		Y6	D	3-2	34-41-11	D01409		33			D00119	Y		YL951-YR328
I	2004R	20		Y6	D	0-0	34-41-11	D01409		34			D00119	X		ALL
I	2004Z				D	0-0	34-41-11	D01409		32			D00119	DED		ALL
I	2005B	20		Y6	H	3-1	34-41-11	D01409		30			D00119	F-		YC051-YD170
I	2005B	20		Y6	H	3-2	34-41-11	D01409		30			D00119	F-		YL951-YR328
I	2005R	20		Y6	H	0-0	34-41-11	D01409		31			D00119	E-		ALL
I	2005Z				H	0-0	34-41-11	D01409		29			D00119	DED		ALL
I	2006B	20		HB	I	3-1	34-41-11	D01409		26			D00119	Z-		YC051-YD170
I	2006B	20		HB	I	3-2	34-41-11	D01409		26			D00119	Z-		YL951-YR328
I	2006R	20		HB	I	0-0	34-41-11	D01409		25			D00119	I-		ALL
I	3001B	20		Y7	E	3-1	34-41-11	D01409		8			D00119	E		YC051-YD170
I	3001B	20		Y7	E	3-2	34-41-11	D01409		8			D00119	E		YL951-YR328
I	3001R	20		Y7	E	0-0	34-41-11	D01409		2			D00119	D		ALL
I	3001Y	20		Y7	E	0-0	34-41-11	D01409		19			D00119	F		ALL
I	3001Z				E	0-0	34-41-11	D01409		18			D00119	DED		ALL
I	3002B	20		Y7	F	3-1	34-41-11	D01409		13			D00119	B		YC051-YD170
I	3002B	20		Y7	F	3-2	34-41-11	D01409		13			D00119	B		YL951-YR328
I	3002R	20		Y7	F	0-0	34-41-11	D01409		14			D00119	A		ALL
I	3002Y	20		Y7	F	0-0	34-41-11	D01409		12			D00119	C		ALL
I	3002Z				F	0-0	34-41-11	D01409		11			D00119	DED		ALL
I	3003B	20		Y7	G	3-1	34-41-11	D01409		37			D00119	H		YC051-YD170
I	3003B	20		Y7	G	3-2	34-41-11	D01409		37			D00119	H		YL951-YR328

WIRE LIST

D280A108

91-21-11

Section W8480

Page 1

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Description			From				To				
Wire No.	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W8489	286A8489			WEATHER RADAR ANTENNA HONEYWELL (continued)											
3003R	20		Y7	G	0-0	34-41-11	D01409	20			D00119	G			ALL
3003Y	20		Y7	G	0-0	34-41-11	D01409	36			D00119	J			ALL
3003Z				G	0-0	34-41-11	D01409	35			D00119	DED			ALL
YAAA					0-0	34-41-11	D01409	PER			D00119	PER			ALL

For training purposes only!

WIRE LIST

D280A108

91-21-11

Section W8480

Page 2 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No.	Part Number			Fam	Description		From				To					
	Wire No.	GA	CO TY		FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity	
W8524	286A8524				AFT RIGHT SIDE WHEEL WELL AREA											
0501	18		HA		1-2	29-32-11	D02676		1			GD00246	ST..	E		YC051-YD152
0501	18		HA		1-4	29-32-11	D02676		1			GD00246	ST..	E		YD153-YR328
0513	18		HA		6-9	49-62-11	D46050P		1			D48080P		1		YC051-YD152
0513	18		HA		7-1	49-62-11	D46050P		1			D48080P		1		YD153-YR328
0514	18		HA		6-9	49-62-11	D46050P		2			D48080P		2		YC051-YD152
0514	18		HA		7-1	49-62-11	D46050P		2			D48080P		2		YD153-YR328
2001B	18		HF	GA	9-0	29-32-11	D02676		2			D46050P		4		YC051-YD152
2001B	18		HF	GA	7-11	29-32-11	D02676		2			D46050P		4		YD153-YR328
2001R	18		HF	GA	0-0	29-32-11	D02676		3			D46050P		3		ALL
2001Z				GA	0-0	29-32-11	GD00246	ST..	E			D46050P	S/R			ALL
2201B	18		HF	KA	6-2	32-41-11	D46050P		10			D00932		2		YC051-YD152
2201B	18		HF	KA	5-3	32-41-11	D46050P		10			D00932		2		YD153-YR328
2201R	18		HF	KA	0-0	32-41-11	D46050P		9			D00932		1		ALL
2201Z				KA	0-0	32-41-11	D46050P	S/R				D00932	S/R			ALL
2202B	18		HQ	KB	6-9	24-22-31	D48080P		15			D46050P		15		YC051-YD152
2202B	18		HQ	KB	7-1	24-22-31	D48080P		15			D46050P		15		YD153-YR328
2202R	18		HQ	KB	0-0	24-22-31	D48080P		16			D46050P		16		ALL
2202Z				KB	0-0	24-22-31	D48080P	DED				D46050P	DED			ALL
6001R	18		QZ		6-9	26-11-31	D46050P		11			D48080P		11		YC051-YD152
6001R	18		QZ		7-1	26-11-31	D46050P		11			D48080P		11		YD153-YR328
6002R	18		QZ		6-9	26-11-31	D46050P		12			D48080P		12		YC051-YD152
6002R	18		QZ		7-1	26-11-31	D46050P		12			D48080P		12		YD153-YR328
6003R	18		QZ		6-9	26-11-31	D46050P		13			D48080P		13		YC051-YD152
6003R	18		QZ		7-1	26-11-31	D46050P		13			D48080P		13		YD153-YR328
6004R	18		QZ		1-8	26-11-31	GD00138	DC..	E			D48080P		10		YC051-YD152
6004R	18		QZ		1-3	26-11-31	GD00138	DC..	E			D48080P		10		YD153-YR328
6005R	18		9P		6-7	26-11-31	D46050P		19			M00277	-	D		ALL
6006R	18		9P		6-8	26-11-31	D46050P		18			M00277	+	C		YC051-YD152
6006R	18		9P		6-9	26-11-31	D46050P		18			M00277	+	C		YD153-YR328
6007R	18		QZ		6-9	26-21-11	D46050P		7			D48080P		7		YC051-YD152
6007R	18		QZ		7-1	26-21-11	D46050P		7			D48080P		7		YD153-YR328
6008R	18		QZ		6-9	26-21-11	D46050P		8			D48080P		8		YC051-YD152
6008R	18		QZ		7-1	26-21-11	D46050P		8			D48080P		8		YD153-YR328

WIRE LIST

D280A108

91-21-11

Section W8520

Page 1 End

Nov 12/2012



737-700/800 WIRING DIAGRAM MANUAL

Bundle No. Wire No.	Part Number			Description			From				To				
	GA	CO	TY	Fam	FT-IN	Diagram	Equip	Term	Type	Splice	Equip	Term	Type	Splice	Effectivity
W8538	286A8538			STANDBY HYD PUMP											
0501	12		CQ		80-6	29-22-11	D11740		A		D00812		A		YC051-YD158
0501	12		CQ		80-7	29-22-11	D11740		A		D00812		A		YD160-YL952
0501	12		CQ		80-5	29-22-11	D11740		A		D00812		A		YL953-YL999, YR301-YR328
0501	12		CQ		70-3	29-22-11	D11740		A		D00812		A		YN231-YN233
0501	12		CQ		70-4	29-22-11	D11740		A		D00812		A		YN234-YN501
0502	12		CQ		80-6	29-22-11	D11740		B		D00812		B		YC051-YD158
0502	12		CQ		80-7	29-22-11	D11740		B		D00812		B		YD160-YL952
0502	12		CQ		80-5	29-22-11	D11740		B		D00812		B		YL953-YL999, YR301-YR328
0502	12		CQ		70-3	29-22-11	D11740		B		D00812		B		YN231-YN233
0502	12		CQ		70-4	29-22-11	D11740		B		D00812		B		YN234-YN501
0503	12		CQ		80-6	29-22-11	D11740		C		D00812		C		YC051-YD158
0503	12		CQ		80-7	29-22-11	D11740		C		D00812		C		YD160-YL952
0503	12		CQ		80-5	29-22-11	D11740		C		D00812		C		YL953-YL999, YR301-YR328
0503	12		CQ		70-3	29-22-11	D11740		C		D00812		C		YN231-YN233
0503	12		CQ		70-4	29-22-11	D11740		C		D00812		C		YN234-YN501

WIRE LIST

D280A108

91-21-11

Section W8530

Page 1 End

Nov 12/2012